

# L4Re Operating System Framework

Generated on Mon Mar 16 2026 12:35:20 for L4Re Operating System Framework by Doxygen  
1.15.0

Mon Mar 16 2026 12:35:20



<b>1 Overview</b>	<b>1</b>
<b>2 Introduction</b>	<b>3</b>
2.1 L4Re Microkernel	3
2.1.1 Communication	3
2.1.2 Kernel Objects	4
2.2 L4Re System Structure	4
2.3 L4Re Runtime Environment	6
<b>3 Programming for L4Re</b>	<b>7</b>
3.1 L4 Inter-Process Communication (IPC)	7
3.1.1 IPC mechanism	8
3.1.1.1 IPC Flags	8
3.1.1.2 Partner capability selector	9
3.1.1.3 IPC Label	9
3.1.1.4 IPC Message Tag	9
3.1.1.5 IPC Timeouts	10
3.1.1.6 User-level Thread Control Block	11
3.1.1.7 Transfer of Typed Send Items	13
3.1.2 Examples	13
3.1.2.1 User Thread to Kernel Object	14
3.1.2.2 User Thread to User Thread	14
3.1.2.3 User Thread to User Object	16
3.2 Kernel ABI	16
3.2.1 Capability selector and flags	17
3.2.2 Label	17
3.2.3 Message tag	17
3.2.4 Timeouts	18
3.2.5 User-level thread control block (UTCB)	19
3.2.5.1 Buffer descriptor register	19
3.2.6 Typed message items	20
3.2.6.1 Flexpages	20
3.2.6.2 Send items	21
3.2.6.3 Receive items	21
3.2.6.4 Return items	22
3.3 Capabilities and Naming	23
3.4 Spaces and Mappings	24
3.5 Initial Environment and Application Bootstrapping	25
3.5.1 Configuring an application before startup	26
3.5.2 Connecting clients and servers	26
3.6 Memory management - Data Spaces and the Region Map	27
3.6.1 User-level paging	27
3.6.1.1 Data spaces	27

3.6.1.2 Virtual Memory Handling	27
3.6.1.3 Memory Allocation	27
3.7 Program Input and Output	28
3.8 Initial Memory Allocator and Factory	28
3.9 Application and Server Building Blocks	28
3.9.1 Creating Additional Application Threads	28
3.9.2 Providing a Service	29
3.10 Pthread Support	29
3.11 Interface Definition Language	30
3.11.1 Parameter types for RPC	31
3.11.2 Server Side Interface	32
3.11.3 RPC Return Types	32
3.11.4 RPC Method Declaration	33
3.12 L4Re Build System	33
3.12.1 Building L4Re	34
3.12.2 Writing BID Make Files	35
3.12.3 prog.mk - Application Role	35
3.12.4 include.mk - Header File Role	38
3.12.5 test.mk - Test Application Role	39
3.13 Kernel Factory	46
3.13.1 Passing parameters for the create stream	46
<b>4 L4Re Servers</b>	<b>49</b>
4.1 Sigma0, the Root-Pager	50
4.1.1 Factory	51
4.2 Moe	51
4.2.1 Moe objects	51
4.2.1.1 Factory	51
4.3 Ned, the Init Process	56
4.3.1 Lua Bindings for L4Re	57
4.3.1.1 Tutorial	57
4.3.1.2 Capabilities in Lua	57
4.3.1.3 Access to L4Re::Env Capabilities	57
4.3.1.4 Constants	57
4.3.1.5 Application Startup Details	58
4.3.1.6 Reacting on task termination	60
4.3.1.7 Control scheduling	60
4.3.1.8 Access to the kernel debugger	60
4.3.1.9 Using the interactive ned prompt	61
4.3.2 Command Line Options	61
4.4 Io, the Io Server	61
4.5 Virtio Net P2P, a virtual network point-to-point link	67



4.6 Virtio Net Switch, a virtual network switch . . . . .	69
4.7 Uvmm, the virtual machine monitor . . . . .	72
4.7.1 RAM configuration . . . . .	81
4.8 RTC driver . . . . .	82
4.9 Mag, the GUI Multiplexer . . . . .	82
4.10 Cons, the Console Multiplexer . . . . .	85
<b>5 uvmm_dtg The device tree generator for Uvmm</b>	<b>89</b>
<b>6 Bootstrap, the L4 kernel bootstrapper</b>	<b>91</b>
<b>7 Deprecated List</b>	<b>95</b>
<b>8 Topic Index</b>	<b>97</b>
8.1 Topics . . . . .	97
<b>9 Namespace Index</b>	<b>101</b>
9.1 Namespace List . . . . .	101
<b>10 Hierarchical Index</b>	<b>103</b>
10.1 Class Hierarchy . . . . .	103
<b>11 Data Structure Index</b>	<b>117</b>
11.1 Data Structures . . . . .	117
<b>12 File Index</b>	<b>135</b>
12.1 File List . . . . .	135
<b>13 Topic Documentation</b>	<b>149</b>
13.1 Base API . . . . .	149
13.1.1 Detailed Description . . . . .	152
13.1.2 Basic Macros . . . . .	152
13.1.2.1 Detailed Description . . . . .	154
13.1.2.2 Macro Definition Documentation . . . . .	154
13.1.2.3 Function Documentation . . . . .	156
13.1.3 Fiasco extensions . . . . .	157
13.1.3.1 Detailed Description . . . . .	158
13.1.3.2 Function Documentation . . . . .	159
13.1.3.3 Kernel Debugger . . . . .	161
13.1.3.4 Kernel Information Dump . . . . .	169
13.1.3.5 Kernel Tracing . . . . .	170
13.1.4 Flexpages . . . . .	173
13.1.4.1 Detailed Description . . . . .	175
13.1.4.2 Enumeration Type Documentation . . . . .	175
13.1.4.3 Function Documentation . . . . .	179
13.1.5 C++ IPC Interface Definition . . . . .	191

13.1.5.1 Detailed Description . . . . .	191
13.1.5.2 Internal Helpers . . . . .	192
13.1.6 Cache Consistency . . . . .	192
13.1.6.1 Detailed Description . . . . .	193
13.1.6.2 Function Documentation . . . . .	193
13.1.7 Memory related . . . . .	196
13.1.7.1 Detailed Description . . . . .	197
13.1.7.2 Macro Definition Documentation . . . . .	198
13.1.7.3 Enumeration Type Documentation . . . . .	200
13.1.7.4 Function Documentation . . . . .	201
13.1.8 Error codes . . . . .	205
13.1.8.1 Detailed Description . . . . .	206
13.1.8.2 Enumeration Type Documentation . . . . .	206
13.1.9 Object Invocation . . . . .	207
13.1.9.1 Detailed Description . . . . .	209
13.1.9.2 Timeouts during IPC . . . . .	209
13.1.9.3 Macro Definition Documentation . . . . .	209
13.1.9.4 Function Documentation . . . . .	210
13.1.9.5 Message Items . . . . .	225
13.1.9.6 Timeouts . . . . .	232
13.1.9.7 Error Handling . . . . .	241
13.1.9.8 Realtime API . . . . .	247
13.1.9.9 Message Tag . . . . .	247
13.1.9.10 Virtual Registers (UTCBS) . . . . .	260
13.1.10 Kernel Objects . . . . .	273
13.1.10.1 Detailed Description . . . . .	275
13.1.10.2 IPC-Gate API . . . . .	275
13.1.10.3 DMA space . . . . .	280
13.1.10.4 L4 kernel object type information . . . . .	280
13.1.10.5 Factory . . . . .	282
13.1.10.6 Virtual Machines . . . . .	293
13.1.10.7 Interrupt controller . . . . .	314
13.1.10.8 IRQs . . . . .	331
13.1.10.9 Platform Control C API . . . . .	346
13.1.10.10 Scheduler . . . . .	352
13.1.10.11 Kernel-provided semaphore . . . . .	360
13.1.10.12 Task . . . . .	362
13.1.10.13 Thread . . . . .	374
13.1.10.14 Thread groups . . . . .	408
13.1.10.15 Virtual Console . . . . .	410
13.1.11 Kernel Interface Page . . . . .	425
13.1.11.1 Detailed Description . . . . .	427

13.1.11.2 Typedef Documentation	427
13.1.11.3 Enumeration Type Documentation	427
13.1.11.4 Function Documentation	428
13.1.11.5 Memory descriptors (C version)	432
13.1.12 Capabilities	437
13.1.12.1 Detailed Description	438
13.1.12.2 Typedef Documentation	438
13.1.12.3 Enumeration Type Documentation	439
13.1.12.4 Function Documentation	439
13.1.13 Memory Operations	441
13.1.13.1 Detailed Description	442
13.1.13.2 Enumeration Type Documentation	442
13.1.13.3 Function Documentation	443
13.1.14 Integer Types	444
13.1.14.1 Detailed Description	446
13.2 EDID parsing functionality	446
13.2.1 Detailed Description	446
13.2.2 Enumeration Type Documentation	446
13.2.2.1 Libedid_consts	446
13.2.3 Function Documentation	447
13.2.3.1 libedid_check_header()	447
13.2.3.2 libedid_checksum()	447
13.2.3.3 libedid_dump()	448
13.2.3.4 libedid_dump_standard_timings()	448
13.2.3.5 libedid_num_ext_blocks()	448
13.2.3.6 libedid_pnp_id()	449
13.2.3.7 libedid_prefered_resolution()	449
13.2.3.8 libedid_revision()	449
13.2.3.9 libedid_version()	450
13.3 IO interface	450
13.3.1 Detailed Description	451
13.3.2 Typedef Documentation	451
13.3.2.1 l4io_resource_t	451
13.3.3 Enumeration Type Documentation	451
13.3.3.1 l4io_device_types_t	451
13.3.3.2 l4io_iomem_flags_t	452
13.3.3.3 l4io_resource_types_t	452
13.3.4 Function Documentation	453
13.3.4.1 l4io_has_resource()	453
13.3.4.2 l4io_lookup_device()	453
13.3.4.3 l4io_lookup_resource()	454
13.3.4.4 l4io_release_iomem()	454

13.3.4.5 l4io_release_ioport()	455
13.3.4.6 l4io_request_iomem()	455
13.3.4.7 l4io_request_iomem_region()	456
13.3.4.8 l4io_request_ioport()	457
13.3.4.9 l4io_request_resource_iomem()	457
13.4 IPC Helpers	458
13.4.1 Detailed Description	458
13.4.2 Function Documentation	458
13.4.2.1 throw_ipc_exception() [1/2]	458
13.4.2.2 throw_ipc_exception() [2/2]	459
13.5 IRQ handling library	459
13.5.1 Detailed Description	460
13.5.2 Interface using direct functionality.	460
13.5.2.1 Detailed Description	461
13.5.2.2 Function Documentation	461
13.5.2.3 Interface using direct functionality.	465
13.5.3 Interface for asynchronous ISR handlers.	467
13.5.3.1 Detailed Description	468
13.5.3.2 Function Documentation	468
13.5.3.3 Interface for asynchronous ISR handlers with a given IRQ capability.	469
13.6 L4 IPC Opcodes	470
13.6.1 Detailed Description	471
13.6.2 Enumeration Type Documentation	471
13.6.2.1 L4_icu_opcode	471
13.6.2.2 L4_ipc_gate_ops	472
13.6.2.3 L4_platform_ctl_ops	473
13.6.2.4 L4_task_ops	473
13.6.2.5 L4_thread_ops	473
13.6.2.6 L4_vcon_ops	474
13.7 L4 VIRTIO Interface	475
13.7.1 Detailed Description	475
13.7.2 L4 VIRTIO Transport Layer	475
13.7.2.1 Detailed Description	477
13.7.2.2 Typedef Documentation	477
13.7.2.3 Enumeration Type Documentation	478
13.7.2.4 Function Documentation	480
13.7.3 L4 VIRTIO Block Device	484
13.7.3.1 Detailed Description	485
13.7.3.2 Enumeration Type Documentation	485
13.7.4 L4 VIRTIO Input Device	486
13.7.4.1 Detailed Description	486
13.7.5 L4 VIRTIO Network Device	486

13.7.5.1 Detailed Description . . . . .	487
13.8 L4 Vbus functions . . . . .	487
13.8.1 Detailed Description . . . . .	488
13.8.2 Enumeration Type Documentation . . . . .	489
13.8.2.1 L4vbus_dma_domain_assign_flags . . . . .	489
13.8.3 Function Documentation . . . . .	489
13.8.3.1 l4vbus_assign_dma_domain() . . . . .	489
13.8.3.2 l4vbus_get_adr() . . . . .	490
13.8.3.3 l4vbus_get_device() . . . . .	490
13.8.3.4 l4vbus_get_device_by_hid() . . . . .	491
13.8.3.5 l4vbus_get_hid() . . . . .	492
13.8.3.6 l4vbus_get_next_device() . . . . .	493
13.8.3.7 l4vbus_get_resource() . . . . .	494
13.8.3.8 l4vbus_is_compatible() . . . . .	494
13.8.3.9 l4vbus_release_ioport() . . . . .	495
13.8.3.10 l4vbus_request_ioport() . . . . .	496
13.8.3.11 l4vbus_vicu_get_cap() . . . . .	497
13.8.4 L4vbus GPIO functions . . . . .	497
13.8.4.1 Detailed Description . . . . .	498
13.8.4.2 Enumeration Type Documentation . . . . .	498
13.8.4.3 Function Documentation . . . . .	499
13.8.5 L4vbus PCI functions . . . . .	508
13.8.5.1 Detailed Description . . . . .	508
13.8.5.2 Function Documentation . . . . .	508
13.8.6 L4vbus power management functions . . . . .	514
13.8.6.1 Detailed Description . . . . .	514
13.8.6.2 Function Documentation . . . . .	514
13.9 L4Re C Interface . . . . .	516
13.9.1 Detailed Description . . . . .	517
13.9.2 L4Re Util C Interface . . . . .	518
13.9.3 Dataspace interface . . . . .	518
13.9.3.1 Detailed Description . . . . .	519
13.9.3.2 Enumeration Type Documentation . . . . .	519
13.9.3.3 Function Documentation . . . . .	520
13.9.4 Debug interface . . . . .	524
13.9.4.1 Detailed Description . . . . .	524
13.9.4.2 Function Documentation . . . . .	524
13.9.5 DMA Space Interface . . . . .	525
13.9.5.1 Detailed Description . . . . .	525
13.9.5.2 Typedef Documentation . . . . .	526
13.9.5.3 Function Documentation . . . . .	526
13.9.6 Event interface . . . . .	529

13.9.6.1 Detailed Description . . . . .	529
13.9.6.2 Function Documentation . . . . .	530
13.9.7 Log interface . . . . .	532
13.9.7.1 Detailed Description . . . . .	533
13.9.7.2 Function Documentation . . . . .	533
13.9.8 Memory allocator . . . . .	535
13.9.8.1 Detailed Description . . . . .	536
13.9.8.2 Enumeration Type Documentation . . . . .	536
13.9.8.3 Function Documentation . . . . .	536
13.9.9 Namespace interface . . . . .	540
13.9.9.1 Detailed Description . . . . .	541
13.9.9.2 Enumeration Type Documentation . . . . .	541
13.9.9.3 Function Documentation . . . . .	541
13.9.10 Parent interface . . . . .	544
13.9.11 Region map interface . . . . .	544
13.9.11.1 Detailed Description . . . . .	545
13.9.11.2 Enumeration Type Documentation . . . . .	545
13.9.11.3 Function Documentation . . . . .	546
13.9.12 Capability allocator . . . . .	559
13.9.12.1 Detailed Description . . . . .	560
13.9.12.2 Function Documentation . . . . .	560
13.9.13 Kumem allocator utility . . . . .	560
13.9.14 Video API . . . . .	561
13.9.14.1 Detailed Description . . . . .	562
13.9.14.2 Typedef Documentation . . . . .	562
13.9.14.3 Enumeration Type Documentation . . . . .	563
13.9.14.4 Function Documentation . . . . .	563
13.9.15 Initial Environment . . . . .	569
13.9.15.1 Detailed Description . . . . .	570
13.9.15.2 Function Documentation . . . . .	570
13.10 L4Re C++ Interface . . . . .	574
13.10.1 Detailed Description . . . . .	576
13.10.2 L4Re Util C++ Interface . . . . .	576
13.10.2.1 Detailed Description . . . . .	577
13.10.2.2 L4Re Capability API . . . . .	577
13.10.2.3 Kumem utilities . . . . .	579
13.10.3 Console API . . . . .	581
13.10.3.1 Detailed Description . . . . .	581
13.10.4 Debugging API . . . . .	581
13.10.4.1 Detailed Description . . . . .	582
13.10.5 L4Re ELF Auxiliary Information . . . . .	582
13.10.5.1 Detailed Description . . . . .	583

13.10.5.2 Macro Definition Documentation . . . . .	583
13.10.5.3 Enumeration Type Documentation . . . . .	584
13.10.6 Event API . . . . .	584
13.10.6.1 Detailed Description . . . . .	585
13.10.7 Auxiliary data . . . . .	585
13.10.7.1 Detailed Description . . . . .	586
13.10.8 Logging interface . . . . .	586
13.10.8.1 Detailed Description . . . . .	586
13.10.9 Name-space API . . . . .	586
13.10.9.1 Detailed Description . . . . .	587
13.10.10 Parent API . . . . .	587
13.10.10.1 Detailed Description . . . . .	587
13.10.11 L4Re Protocol identifiers . . . . .	588
13.10.11.1 Detailed Description . . . . .	588
13.10.11.2 Enumeration Type Documentation . . . . .	589
13.10.12 Region map API . . . . .	589
13.10.12.1 Detailed Description . . . . .	590
13.10.13 Video API . . . . .	590
13.10.13.1 Detailed Description . . . . .	591
13.10.14 C++ Exceptions . . . . .	591
13.10.14.1 Detailed Description . . . . .	592
13.10.15 Vbus API . . . . .	592
13.10.15.1 Detailed Description . . . . .	593
13.11 L4SHM-based ring buffer implementation . . . . .	593
13.11.1 Detailed Description . . . . .	594
13.11.2 Sender . . . . .	594
13.11.3 Receiver . . . . .	594
13.11.4 Internal . . . . .	594
13.11.4.1 Detailed Description . . . . .	595
13.11.4.2 Macro Definition Documentation . . . . .	595
13.12 Shared Memory Library . . . . .	596
13.12.1 Detailed Description . . . . .	597
13.12.2 Function Documentation . . . . .	598
13.12.2.1 l4shmc_area_overhead() . . . . .	598
13.12.2.2 l4shmc_area_size() . . . . .	598
13.12.2.3 l4shmc_area_size_free() . . . . .	598
13.12.2.4 l4shmc_attach() . . . . .	599
13.12.2.5 l4shmc_chunk_overhead() . . . . .	599
13.12.2.6 l4shmc_connect_chunk_signal() . . . . .	600
13.12.2.7 l4shmc_create() . . . . .	600
13.12.2.8 l4shmc_get_client_nr() . . . . .	601
13.12.2.9 l4shmc_get_initialized_clients() . . . . .	601

13.12.2.10 l4shmc_mark_client_initialized()	602
13.12.3 Chunks	602
13.12.3.1 Detailed Description	603
13.12.3.2 Function Documentation	603
13.12.3.3 Producer	607
13.12.3.4 Consumer	610
13.12.4 Signals	615
13.12.4.1 Detailed Description	615
13.12.4.2 Function Documentation	615
13.12.4.3 Producer	618
13.12.4.4 Consumer	619
13.13 Sigma0 API	623
13.13.1 Detailed Description	624
13.13.2 Enumeration Type Documentation	624
13.13.2.1 l4sigma0_return_flags_t	624
13.13.3 Function Documentation	625
13.13.3.1 l4sigma0_debug_dump()	625
13.13.3.2 l4sigma0_map_anypage()	625
13.13.3.3 l4sigma0_map_errstr()	626
13.13.3.4 l4sigma0_map_iomem()	626
13.13.3.5 l4sigma0_map_kip()	627
13.13.3.6 l4sigma0_map_mem()	627
13.13.4 Internal constants	628
13.13.4.1 Detailed Description	629
13.14 Small C++ Template Library	629
13.14.1 Detailed Description	630
13.14.2 Function Documentation	630
13.14.2.1 clamp()	630
13.14.2.2 max() [1/2]	631
13.14.2.3 max() [2/2]	631
13.14.2.4 min() [1/2]	632
13.14.2.5 min() [2/2]	632
13.14.2.6 operator new()	632
13.15 The L4Re IPC Framework	633
13.15.1 Detailed Description	633
13.15.2 Server-Side IPC framework	633
13.15.2.1 Detailed Description	634
13.15.2.2 Enumeration Type Documentation	635
13.16 Utility Functions	635
13.16.1 Detailed Description	637
13.16.2 Function Documentation	638
13.16.2.1 l4_sleep()	638



13.16.2.2 I4_touch_ro()	638
13.16.2.3 I4_touch_rw()	639
13.16.2.4 I4_usleep()	640
13.16.2.5 I4util_micros2I4to()	640
13.16.2.6 I4util_splitlog2_hdl()	641
13.16.2.7 I4util_splitlog2_size()	641
13.16.3 CPU related functions	642
13.16.3.1 Detailed Description	643
13.16.3.2 Function Documentation	643
13.16.4 IA32 Port I/O API	645
13.16.4.1 Detailed Description	646
13.16.4.2 Function Documentation	646
13.16.5 Timestamp Counter	651
13.16.5.1 Detailed Description	652
13.16.5.2 Function Documentation	652
13.16.6 Atomic Instructions	658
13.16.6.1 Detailed Description	660
13.16.6.2 Function Documentation	660
13.16.7 Internal functions	676
13.16.7.1 Detailed Description	676
13.16.8 Bit Manipulation	676
13.16.8.1 Detailed Description	677
13.16.8.2 Function Documentation	677
13.16.9 ELF binary format	683
13.16.9.1 Detailed Description	689
13.16.9.2 Macro Definition Documentation	689
13.16.9.3 Enumeration Type Documentation	691
13.16.10 Kernel Interface Page API	708
13.16.10.1 Detailed Description	708
13.16.10.2 Macro Definition Documentation	708
13.16.10.3 Function Documentation	709
13.16.11 Comfortable Command Line Parsing	710
13.16.11.1 Detailed Description	710
13.16.11.2 Function Documentation	710
13.16.12 Random number support	712
13.16.12.1 Detailed Description	712
13.16.12.2 Function Documentation	712
13.16.13 Low-Level Thread Functions	713
13.17 Virtio Net Switch	713
13.17.1 Detailed Description	714
13.18 vCPU Support Library	714
13.18.1 Detailed Description	715

13.18.2 Function Documentation	715
13.18.2.1 l4vcpu_irq_disable()	715
13.18.2.2 l4vcpu_irq_disable_save()	716
13.18.2.3 l4vcpu_irq_enable()	717
13.18.2.4 l4vcpu_irq_restore()	718
13.18.2.5 l4vcpu_is_irq_entry()	719
13.18.2.6 l4vcpu_is_page_fault_entry()	719
13.18.2.7 l4vcpu_print_state()	720
13.18.2.8 l4vcpu_wait_for_event()	720
13.18.3 Extended vCPU support	721
13.18.3.1 Detailed Description	722
13.18.3.2 Function Documentation	722
<b>14 Namespace Documentation</b>	<b>723</b>
14.1 cxx Namespace Reference	723
14.1.1 Detailed Description	725
14.1.2 Function Documentation	726
14.1.2.1 access_once()	726
14.1.2.2 gcd()	727
14.1.2.3 lcm()	728
14.1.2.4 write_now()	729
14.2 cxx::Bits Namespace Reference	729
14.2.1 Detailed Description	730
14.3 Enum_bitops Namespace Reference	730
14.3.1 Detailed Description	730
14.4 Enum_bitops_impl Namespace Reference	730
14.4.1 Detailed Description	731
14.5 L4 Namespace Reference	731
14.5.1 Detailed Description	735
14.5.2 Enumeration Type Documentation	735
14.5.2.1 anonymous enum	735
14.5.3 Function Documentation	736
14.5.3.1 cap_cast() [1/2]	736
14.5.3.2 cap_cast() [2/2]	737
14.5.3.3 cap_dynamic_cast()	738
14.5.3.4 cap_reinterpret_cast() [1/2]	739
14.5.3.5 cap_reinterpret_cast() [2/2]	740
14.5.3.6 round_order()	740
14.5.3.7 trunc_order()	741
14.6 L4::lpc Namespace Reference	742
14.6.1 Detailed Description	744
14.6.2 Function Documentation	744

14.6.2.1 buf_cp_in()	744
14.6.2.2 buf_cp_out()	745
14.6.2.3 buf_in()	746
14.6.2.4 make_cap()	746
14.6.2.5 make_cap_full()	747
14.6.2.6 make_cap_rw()	748
14.6.2.7 make_cap_rws()	749
14.6.2.8 msg_ptr()	749
14.6.2.9 read()	749
14.6.2.10 str_cp_in()	750
14.7 L4::lpc::Msg Namespace Reference	750
14.7.1 Detailed Description	751
14.7.2 Enumeration Type Documentation	752
14.7.2.1 anonymous enum	752
14.7.3 Function Documentation	752
14.7.3.1 align_to() [1/2]	752
14.7.3.2 align_to() [2/2]	753
14.7.3.3 check_size() [1/2]	754
14.7.3.4 check_size() [2/2]	754
14.7.3.5 msg_add()	755
14.7.3.6 msg_get()	756
14.8 L4::lpc_svr Namespace Reference	757
14.8.1 Detailed Description	758
14.9 L4::Typeid Namespace Reference	758
14.9.1 Detailed Description	758
14.10 L4::Types Namespace Reference	758
14.10.1 Detailed Description	760
14.10.2 Function Documentation	760
14.10.2.1 declval()	760
14.11 L4Re Namespace Reference	760
14.11.1 Detailed Description	762
14.11.2 Typedef Documentation	763
14.11.2.1 Shared_cap	763
14.11.2.2 Shared_del_cap	763
14.11.2.3 Unique_cap	764
14.11.2.4 Unique_del_cap	764
14.11.3 Function Documentation	765
14.11.3.1 chkcap()	765
14.11.3.2 chkipc()	766
14.11.3.3 chksys() [1/3]	767
14.11.3.4 chksys() [2/3]	768
14.11.3.5 chksys() [3/3]	769

14.11.3.6	<a href="#">make_shared_cap()</a>	770
14.11.3.7	<a href="#">make_shared_del_cap()</a>	771
14.11.3.8	<a href="#">make_unique_cap()</a>	772
14.11.3.9	<a href="#">make_unique_del_cap()</a>	773
14.11.3.10	<a href="#">throw_error()</a>	773
14.12	<a href="#">L4Re::Util Namespace Reference</a>	775
14.12.1	<a href="#">Detailed Description</a>	777
14.12.2	<a href="#">Typedef Documentation</a>	778
14.12.2.1	<a href="#">Shared_cap</a>	778
14.12.2.2	<a href="#">Shared_del_cap</a>	778
14.12.2.3	<a href="#">Unique_cap</a>	779
14.12.2.4	<a href="#">Unique_del_cap</a>	780
14.12.3	<a href="#">Function Documentation</a>	780
14.12.3.1	<a href="#">make_shared_cap()</a>	780
14.12.3.2	<a href="#">make_shared_del_cap()</a>	781
14.12.3.3	<a href="#">make_unique_cap()</a>	781
14.12.3.4	<a href="#">make_unique_del_cap()</a>	782
14.13	<a href="#">L4Re::Vfs Namespace Reference</a>	782
14.13.1	<a href="#">Detailed Description</a>	783
14.14	<a href="#">L4vbus Namespace Reference</a>	783
14.14.1	<a href="#">Detailed Description</a>	783
14.15	<a href="#">L4virtio Namespace Reference</a>	784
14.15.1	<a href="#">Detailed Description</a>	784
<b>15</b>	<b>Data Structure Documentation</b>	<b>785</b>
15.1	<a href="#">Buffer Struct Reference</a>	785
15.1.1	<a href="#">Detailed Description</a>	787
15.2	<a href="#">cxx::arith::Ld&lt; V &gt; Struct Template Reference</a>	787
15.2.1	<a href="#">Detailed Description</a>	787
15.3	<a href="#">cxx::Avl_map&lt; KEY_TYPE, DATA_TYPE, COMPARE, ALLOC &gt; Class Template Reference</a>	788
15.3.1	<a href="#">Detailed Description</a>	791
15.3.2	<a href="#">Constructor &amp; Destructor Documentation</a>	792
15.3.2.1	<a href="#">Avl_map()</a>	792
15.3.3	<a href="#">Member Function Documentation</a>	792
15.3.3.1	<a href="#">emplace()</a>	792
15.3.3.2	<a href="#">insert()</a>	793
15.3.3.3	<a href="#">operator[]()</a> [1/2]	793
15.3.3.4	<a href="#">operator[]()</a> [2/2]	794
15.4	<a href="#">cxx::Avl_set&lt; ITEM_TYPE, COMPARE, ALLOC &gt; Class Template Reference</a>	794
15.4.1	<a href="#">Detailed Description</a>	798
15.5	<a href="#">cxx::Avl_tree&lt; Node, Get_key, Compare &gt; Class Template Reference</a>	798
15.5.1	<a href="#">Detailed Description</a>	803

15.5.2 Member Typedef Documentation	804
15.5.2.1 Iterator	804
15.5.3 Member Function Documentation	804
15.5.3.1 insert()	804
15.5.3.2 remove()	805
15.6 cxx::Avl_tree_node Class Reference	806
15.6.1 Detailed Description	808
15.7 cxx::Base_slab< Obj_size, Slab_size, Max_free, Alloc > Class Template Reference	808
15.7.1 Detailed Description	810
15.7.2 Member Enumeration Documentation	811
15.7.2.1 anonymous enum	811
15.7.3 Member Function Documentation	811
15.7.3.1 alloc()	811
15.7.3.2 free()	811
15.7.3.3 free_objects()	812
15.7.3.4 total_objects()	812
15.8 cxx::Base_slab< Obj_size, Slab_size, Max_free, Alloc >::Slab_i Struct Reference	812
15.8.1 Detailed Description	813
15.9 cxx::Base_slab_static< Obj_size, Slab_size, Max_free, Alloc > Class Template Reference	813
15.9.1 Detailed Description	815
15.9.2 Member Enumeration Documentation	816
15.9.2.1 anonymous enum	816
15.9.3 Member Function Documentation	816
15.9.3.1 alloc()	816
15.9.3.2 free()	817
15.9.3.3 free_objects()	817
15.9.3.4 total_objects()	817
15.10 cxx::Bitfield< T, LSB, MSB > Class Template Reference	818
15.10.1 Detailed Description	820
15.10.2 Member Typedef Documentation	820
15.10.2.1 Bits_type	820
15.10.2.2 Shift_type	820
15.10.3 Member Enumeration Documentation	821
15.10.3.1 anonymous enum	821
15.10.4 Member Function Documentation	821
15.10.4.1 get()	821
15.10.4.2 get_unshifted()	821
15.10.4.3 set()	822
15.10.4.4 set_dirty()	822
15.10.4.5 set_unshifted()	823
15.10.4.6 set_unshifted_dirty()	823
15.10.4.7 val()	824

15.10.4.8 val_dirty()	825
15.10.4.9 val_unshifted()	826
15.11 cxx::Bitfield< T, LSB, MSB >::Value< TT > Class Template Reference	826
15.11.1 Detailed Description	827
15.12 cxx::Bitfield< T, LSB, MSB >::Value_base< TT > Class Template Reference	827
15.12.1 Detailed Description	828
15.13 cxx::Bitfield< T, LSB, MSB >::Value_unshifted< TT > Class Template Reference	828
15.13.1 Detailed Description	829
15.14 cxx::Bitmap< BITS > Class Template Reference	830
15.14.1 Detailed Description	833
15.14.2 Member Function Documentation	833
15.14.2.1 scan_zero()	833
15.15 cxx::Bitmap_base Class Reference	834
15.15.1 Detailed Description	836
15.15.2 Member Enumeration Documentation	837
15.15.2.1 anonymous enum	837
15.15.3 Member Function Documentation	837
15.15.3.1 atomic_clear_bit()	837
15.15.3.2 atomic_get_and_clear()	838
15.15.3.3 atomic_get_and_set()	838
15.15.3.4 atomic_set_bit()	839
15.15.3.5 bit() [1/2]	839
15.15.3.6 bit() [2/2]	840
15.15.3.7 bit_index()	841
15.15.3.8 clear_bit()	842
15.15.3.9 operator[]() [1/2]	843
15.15.3.10 operator[]() [2/2]	843
15.15.3.11 scan_zero()	844
15.15.3.12 set_bit()	845
15.15.3.13 word_index()	845
15.16 cxx::Bitmap_base::Bit Class Reference	847
15.16.1 Detailed Description	847
15.17 cxx::Bitmap_base::Char< BITS > Class Template Reference	847
15.17.1 Detailed Description	848
15.18 cxx::Bitmap_base::Word< BITS > Class Template Reference	848
15.18.1 Detailed Description	849
15.19 cxx::Bits::Avl_map_get_key< KEY_TYPE > Struct Template Reference	849
15.19.1 Detailed Description	849
15.20 cxx::Bits::Avl_set_get_key< KEY_TYPE > Struct Template Reference	850
15.20.1 Detailed Description	850
15.21 cxx::Bits::Avl_set_iter< Node, Key, Node_op > Class Template Reference	850
15.21.1 Detailed Description	852

15.21.2 Constructor & Destructor Documentation	852
15.21.2.1 Avl_set_iter() [1/2]	852
15.21.2.2 Avl_set_iter() [2/2]	853
15.21.3 Member Function Documentation	853
15.21.3.1 operator*()	853
15.21.3.2 operator->()	853
15.22 cxx::Bits::Base_avl_set< ITEM_TYPE, COMPARE, ALLOC, GET_KEY > Class Template Reference	854
15.22.1 Detailed Description	857
15.22.2 Member Enumeration Documentation	857
15.22.2.1 anonymous enum	857
15.22.3 Constructor & Destructor Documentation	857
15.22.3.1 Base_avl_set() [1/2]	857
15.22.3.2 Base_avl_set() [2/2]	858
15.22.4 Member Function Documentation	858
15.22.4.1 begin() [1/2]	858
15.22.4.2 begin() [2/2]	858
15.22.4.3 emplace()	859
15.22.4.4 end() [1/2]	859
15.22.4.5 end() [2/2]	859
15.22.4.6 erase()	860
15.22.4.7 find_node()	860
15.22.4.8 insert()	861
15.22.4.9 lower_bound_node()	861
15.22.4.10 operator=()	862
15.22.4.11 rbegin() [1/2]	862
15.22.4.12 rbegin() [2/2]	862
15.22.4.13 remove()	863
15.22.4.14 rend() [1/2]	863
15.22.4.15 rend() [2/2]	864
15.23 cxx::Bits::Base_avl_set< ITEM_TYPE, COMPARE, ALLOC, GET_KEY >::Node Class Reference	864
15.23.1 Detailed Description	865
15.23.2 Member Function Documentation	865
15.23.2.1 operator*()	865
15.23.2.2 operator->()	865
15.23.2.3 valid()	866
15.24 cxx::Bits::Basic_list< POLICY > Class Template Reference	866
15.24.1 Detailed Description	868
15.24.2 Member Function Documentation	868
15.24.2.1 clear()	868
15.24.2.2 iter()	868
15.25 cxx::Bits::Bst< Node, Get_key, Compare > Class Template Reference	869
15.25.1 Detailed Description	872

15.25.2 Member Function Documentation	872
15.25.2.1 begin() [1/2]	872
15.25.2.2 begin() [2/2]	873
15.25.2.3 dir() [1/2]	874
15.25.2.4 dir() [2/2]	874
15.25.2.5 end() [1/2]	875
15.25.2.6 end() [2/2]	876
15.25.2.7 find()	876
15.25.2.8 find_node()	877
15.25.2.9 lower_bound_node()	877
15.25.2.10 rbegin() [1/2]	878
15.25.2.11 rbegin() [2/2]	879
15.25.2.12 remove_all()	879
15.25.2.13 remove_tree()	880
15.25.2.14 rend() [1/2]	881
15.25.2.15 rend() [2/2]	881
15.26 cxx::Bits::Bst_node Class Reference	882
15.26.1 Detailed Description	884
15.27 cxx::Bits::Direction Struct Reference	884
15.27.1 Detailed Description	885
15.27.2 Member Enumeration Documentation	885
15.27.2.1 Direction_e	885
15.27.3 Member Function Documentation	886
15.27.3.1 operator"!"()	886
15.28 cxx::Bits::Smart_ptr_list< ITEM > Class Template Reference	886
15.28.1 Detailed Description	888
15.28.2 Member Function Documentation	889
15.28.2.1 pop_front()	889
15.29 cxx::Bits::Smart_ptr_list_item< T, STORE_T > Class Template Reference	889
15.29.1 Detailed Description	890
15.30 cxx::Elide_dtor< T > Class Template Reference	891
15.30.1 Detailed Description	891
15.31 cxx::H_list< T, POLICY > Class Template Reference	892
15.31.1 Detailed Description	895
15.31.2 Member Function Documentation	895
15.31.2.1 erase()	895
15.31.2.2 insert()	895
15.31.2.3 insert_after()	896
15.31.2.4 insert_before()	896
15.31.2.5 iter()	897
15.31.2.6 pop_front()	898
15.31.2.7 remove()	898



15.31.2.8 replace()	899
15.32 cxx::H_list_item_t< ELEM_TYPE > Class Template Reference	899
15.32.1 Detailed Description	901
15.32.2 Constructor & Destructor Documentation	901
15.32.2.1 H_list_item_t()	901
15.32.2.2 ~H_list_item_t()	902
15.33 cxx::H_list_t< T > Struct Template Reference	902
15.33.1 Detailed Description	906
15.34 cxx::List< D, Alloc > Class Template Reference	906
15.34.1 Detailed Description	907
15.34.2 Member Function Documentation	907
15.34.2.1 operator[]() [1/2]	907
15.34.2.2 operator[]() [2/2]	908
15.35 cxx::List< D, Alloc >::Iter Class Reference	908
15.35.1 Detailed Description	908
15.36 cxx::List_alloc Class Reference	909
15.36.1 Detailed Description	909
15.36.2 Constructor & Destructor Documentation	910
15.36.2.1 List_alloc()	910
15.36.3 Member Function Documentation	910
15.36.3.1 alloc()	910
15.36.3.2 alloc_max()	911
15.36.3.3 avail()	912
15.36.3.4 free()	912
15.37 cxx::List_item Class Reference	913
15.37.1 Detailed Description	914
15.37.2 Member Function Documentation	914
15.37.2.1 push_back()	914
15.37.2.2 push_front()	915
15.37.2.3 remove()	915
15.38 cxx::List_item::Iter Class Reference	916
15.38.1 Detailed Description	918
15.39 cxx::List_item::T_iter< T, Poly > Class Template Reference	918
15.39.1 Detailed Description	919
15.40 cxx::Lt_functor< Obj > Struct Template Reference	920
15.40.1 Detailed Description	920
15.41 cxx::New_allocator< _Type > Class Template Reference	920
15.41.1 Detailed Description	921
15.42 cxx::Nothrow Class Reference	922
15.42.1 Detailed Description	922
15.43 cxx::Pair< First, Second > Struct Template Reference	922
15.43.1 Detailed Description	924

15.43.2 Constructor & Destructor Documentation	925
15.43.2.1 Pair() [1/2]	925
15.43.2.2 Pair() [2/2]	925
15.44 cxx::Pair_first_compare< Cmp, Typ > Class Template Reference	925
15.44.1 Detailed Description	926
15.44.2 Constructor & Destructor Documentation	926
15.44.2.1 Pair_first_compare()	926
15.44.3 Member Function Documentation	927
15.44.3.1 operator()()	927
15.45 cxx::Ref_obj_list_item< T > Struct Template Reference	927
15.45.1 Detailed Description	929
15.46 cxx::Ref_ptr< T, CNT > Class Template Reference	929
15.46.1 Detailed Description	931
15.46.2 Constructor & Destructor Documentation	932
15.46.2.1 Ref_ptr() [1/3]	932
15.46.2.2 Ref_ptr() [2/3]	932
15.46.2.3 Ref_ptr() [3/3]	933
15.46.3 Member Function Documentation	933
15.46.3.1 get()	933
15.46.3.2 ptr()	933
15.46.3.3 release()	933
15.47 cxx::S_list< T, POLICY > Class Template Reference	934
15.47.1 Detailed Description	936
15.47.2 Member Function Documentation	937
15.47.2.1 pop_front()	937
15.48 cxx::Slab< Type, Slab_size, Max_free, Alloc > Class Template Reference	937
15.48.1 Detailed Description	940
15.48.2 Member Function Documentation	940
15.48.2.1 alloc()	940
15.48.2.2 free()	941
15.49 cxx::Slab_static< Type, Slab_size, Max_free, Alloc > Class Template Reference	942
15.49.1 Detailed Description	945
15.49.2 Member Function Documentation	945
15.49.2.1 alloc()	945
15.50 cxx::static_vector< T, IDX > Class Template Reference	946
15.50.1 Detailed Description	947
15.51 cxx::String Class Reference	947
15.51.1 Detailed Description	951
15.51.2 Constructor & Destructor Documentation	951
15.51.2.1 String()	951
15.51.3 Member Function Documentation	951
15.51.3.1 find()	951

15.51.3.2 from_dec()	952
15.51.3.3 from_hex()	953
15.51.3.4 starts_with()	954
15.52 cxx::Weak_ref< T > Class Template Reference	955
15.52.1 Detailed Description	957
15.53 cxx::Weak_ref_base Class Reference	957
15.53.1 Detailed Description	960
15.54 cxx::Weak_ref_base::List Struct Reference	960
15.54.1 Detailed Description	964
15.55 Elf32_Auxv Struct Reference	964
15.55.1 Detailed Description	964
15.55.2 Field Documentation	965
15.55.2.1 atype	965
15.56 Elf32_Dyn Struct Reference	965
15.56.1 Detailed Description	965
15.56.2 Field Documentation	966
15.56.2.1 d_tag	966
15.57 Elf32_Ehdr Struct Reference	966
15.57.1 Detailed Description	967
15.57.2 Field Documentation	967
15.57.2.1 e_flags	967
15.57.2.2 e_machine	968
15.57.2.3 e_type	968
15.57.2.4 e_version	968
15.58 Elf32_Phdr Struct Reference	969
15.58.1 Detailed Description	969
15.58.2 Field Documentation	970
15.58.2.1 p_flags	970
15.58.2.2 p_type	970
15.59 Elf32_Rel Struct Reference	970
15.59.1 Detailed Description	971
15.60 Elf32_Rela Struct Reference	971
15.60.1 Detailed Description	971
15.61 Elf32_Shdr Struct Reference	972
15.61.1 Detailed Description	973
15.61.2 Field Documentation	973
15.61.2.1 sh_flags	973
15.61.2.2 sh_type	973
15.62 Elf32_Sym Struct Reference	974
15.62.1 Detailed Description	974
15.63 Elf64_Auxv Struct Reference	975
15.63.1 Detailed Description	975

15.63.2 Field Documentation	975
15.63.2.1 atype	975
15.64 Elf64_Dyn Struct Reference	976
15.64.1 Detailed Description	976
15.64.2 Field Documentation	976
15.64.2.1 d_tag	976
15.65 Elf64_Ehdr Struct Reference	977
15.65.1 Detailed Description	978
15.65.2 Field Documentation	978
15.65.2.1 e_flags	978
15.65.2.2 e_machine	978
15.65.2.3 e_type	979
15.65.2.4 e_version	979
15.66 Elf64_Phdr Struct Reference	979
15.66.1 Detailed Description	980
15.66.2 Field Documentation	980
15.66.2.1 p_flags	980
15.66.2.2 p_type	980
15.67 Elf64_Rel Struct Reference	981
15.67.1 Detailed Description	981
15.68 Elf64_Rela Struct Reference	981
15.68.1 Detailed Description	982
15.69 Elf64_Shdr Struct Reference	982
15.69.1 Detailed Description	983
15.69.2 Field Documentation	983
15.69.2.1 sh_flags	983
15.69.2.2 sh_type	983
15.70 Elf64_Sym Struct Reference	984
15.70.1 Detailed Description	984
15.71 Enum_bitops::Enable< T > Struct Template Reference	985
15.71.1 Detailed Description	986
15.72 Enum_bitops::Has_marker< typename, typename > Struct Template Reference	986
15.72.1 Detailed Description	988
15.73 Enum_bitops::Has_marker< T, Void< decltype(enum_bitops_enable(declval< T >()))> > Struct Template Reference	989
15.73.1 Detailed Description	991
15.74 L4::Alloc_list Class Reference	991
15.74.1 Detailed Description	991
15.75 L4::Arm_smccc Class Reference	992
15.75.1 Detailed Description	992
15.75.2 Member Function Documentation	992
15.75.2.1 call()	992

15.76 L4::Base_exception Class Reference . . . . .	994
15.76.1 Detailed Description . . . . .	996
15.77 L4::Basic_registry Class Reference . . . . .	996
15.77.1 Detailed Description . . . . .	997
15.77.2 Member Function Documentation . . . . .	997
15.77.2.1 dispatch() . . . . .	997
15.77.2.2 find() . . . . .	998
15.78 L4::Bounds_error Class Reference . . . . .	999
15.78.1 Detailed Description . . . . .	1001
15.79 L4::Cap< T > Class Template Reference . . . . .	1002
15.79.1 Detailed Description . . . . .	1005
15.79.2 Constructor & Destructor Documentation . . . . .	1006
15.79.2.1 Cap() [ 1 / 4 ] . . . . .	1006
15.79.2.2 Cap() [ 2 / 4 ] . . . . .	1006
15.79.2.3 Cap() [ 3 / 4 ] . . . . .	1006
15.79.2.4 Cap() [ 4 / 4 ] . . . . .	1007
15.79.3 Member Function Documentation . . . . .	1007
15.79.3.1 check_castable_from() . . . . .	1007
15.79.3.2 check_convertible_from() . . . . .	1007
15.79.3.3 copy() . . . . .	1008
15.79.3.4 move() . . . . .	1008
15.80 L4::Cap_base Class Reference . . . . .	1008
15.80.1 Detailed Description . . . . .	1010
15.80.2 Member Enumeration Documentation . . . . .	1011
15.80.2.1 Cap_type . . . . .	1011
15.80.2.2 No_init_type . . . . .	1011
15.80.3 Constructor & Destructor Documentation . . . . .	1011
15.80.3.1 Cap_base() [ 1 / 2 ] . . . . .	1011
15.80.3.2 Cap_base() [ 2 / 2 ] . . . . .	1012
15.80.4 Member Function Documentation . . . . .	1013
15.80.4.1 cap() . . . . .	1013
15.80.4.2 copy() . . . . .	1014
15.80.4.3 fpage() . . . . .	1015
15.80.4.4 is_valid() . . . . .	1016
15.80.4.5 move() . . . . .	1017
15.80.4.6 snd_base() . . . . .	1018
15.80.4.7 validate() [ 1 / 2 ] . . . . .	1019
15.80.4.8 validate() [ 2 / 2 ] . . . . .	1020
15.81 L4::Com_error Class Reference . . . . .	1021
15.81.1 Detailed Description . . . . .	1023
15.81.2 Constructor & Destructor Documentation . . . . .	1024
15.81.2.1 Com_error() . . . . .	1024

15.82 L4::Debugger Class Reference . . . . .	1024
15.82.1 Detailed Description . . . . .	1028
15.82.2 Member Function Documentation . . . . .	1028
15.82.2.1 add_image_info() . . . . .	1028
15.82.2.2 get_object_name() . . . . .	1029
15.82.2.3 global_id() . . . . .	1029
15.82.2.4 kobj_to_id() . . . . .	1030
15.82.2.5 query_log_name() . . . . .	1031
15.82.2.6 query_log_typeid() . . . . .	1031
15.82.2.7 query_object_name() . . . . .	1032
15.82.2.8 set_object_name() . . . . .	1033
15.82.2.9 switch_log() . . . . .	1034
15.83 L4::Element_already_exists Class Reference . . . . .	1034
15.83.1 Detailed Description . . . . .	1037
15.84 L4::Element_not_found Class Reference . . . . .	1038
15.84.1 Detailed Description . . . . .	1040
15.85 L4::Epiface Struct Reference . . . . .	1041
15.85.1 Detailed Description . . . . .	1042
15.85.2 Member Function Documentation . . . . .	1042
15.85.2.1 dispatch() . . . . .	1042
15.85.2.2 get_buffer_demand() . . . . .	1043
15.85.2.3 obj_cap() . . . . .	1044
15.85.2.4 server_iface() . . . . .	1044
15.85.2.5 set_server() . . . . .	1045
15.86 L4::Epiface_t< Derived, IFACE, BASE, bool > Struct Template Reference . . . . .	1046
15.86.1 Detailed Description . . . . .	1048
15.86.2 Member Function Documentation . . . . .	1049
15.86.2.1 dispatch() . . . . .	1049
15.87 L4::Epiface_t0< RPC_IFACE, BASE > Struct Template Reference . . . . .	1049
15.87.1 Detailed Description . . . . .	1051
15.87.2 Member Function Documentation . . . . .	1052
15.87.2.1 obj_cap() . . . . .	1052
15.88 L4::Exception Class Reference . . . . .	1052
15.88.1 Detailed Description . . . . .	1053
15.88.2 Member Function Documentation . . . . .	1053
15.88.2.1 exception() . . . . .	1053
15.89 L4::Exception_tracer Class Reference . . . . .	1054
15.89.1 Detailed Description . . . . .	1055
15.90 L4::Factory Class Reference . . . . .	1055
15.90.1 Detailed Description . . . . .	1059
15.90.2 Member Function Documentation . . . . .	1059
15.90.2.1 create() [1/2] . . . . .	1059

15.90.2.2 create() [2/2]	1060
15.90.2.3 create_factory()	1062
15.90.2.4 create_gate()	1063
15.90.2.5 create_task()	1064
15.90.2.6 create_thread_group()	1065
15.91 L4::Factory::Lstr Struct Reference	1066
15.91.1 Detailed Description	1067
15.91.2 Constructor & Destructor Documentation	1067
15.91.2.1 Lstr()	1067
15.92 L4::Factory::Nil Struct Reference	1068
15.92.1 Detailed Description	1068
15.93 L4::Factory::S Class Reference	1068
15.93.1 Detailed Description	1070
15.93.2 Constructor & Destructor Documentation	1070
15.93.2.1 S() [1/2]	1070
15.93.2.2 S() [2/2]	1070
15.93.2.3 ~S()	1071
15.93.3 Member Function Documentation	1071
15.93.3.1 operator l4_msgtag_t()	1071
15.93.3.2 operator<<() [1/2]	1072
15.93.3.3 operator<<() [2/2]	1072
15.93.3.4 put() [1/5]	1073
15.93.3.5 put() [2/5]	1073
15.93.3.6 put() [3/5]	1074
15.93.3.7 put() [4/5]	1074
15.93.3.8 put() [5/5]	1075
15.94 L4::lcu Class Reference	1075
15.94.1 Detailed Description	1079
15.94.2 Member Function Documentation	1079
15.94.2.1 bind()	1079
15.94.2.2 info()	1080
15.94.2.3 mask()	1081
15.94.2.4 msi_info()	1082
15.94.2.5 set_mode()	1083
15.94.2.6 unbind()	1084
15.95 L4::lcu::Info Class Reference	1085
15.95.1 Detailed Description	1086
15.96 L4::Invalid_capability Class Reference	1087
15.96.1 Detailed Description	1089
15.96.2 Constructor & Destructor Documentation	1089
15.96.2.1 Invalid_capability()	1089
15.96.3 Member Function Documentation	1090

15.96.3.1 cap()	1090
15.97 L4::io_pager Class Reference	1090
15.97.1 Detailed Description	1092
15.97.2 Member Function Documentation	1093
15.97.2.1 io_page_fault()	1093
15.98 L4::lommu Class Reference	1093
15.98.1 Detailed Description	1095
15.98.2 Member Function Documentation	1096
15.98.2.1 bind()	1096
15.98.2.2 unbind()	1097
15.99 L4::IOModifier Class Reference	1098
15.99.1 Detailed Description	1098
15.100 L4::lpc::Array< ELEM_TYPE, LEN_TYPE > Struct Template Reference	1098
15.100.1 Detailed Description	1100
15.101 L4::lpc::Array_in_buf< ELEM_TYPE, LEN_TYPE, MAX > Struct Template Reference	1101
15.101.1 Detailed Description	1103
15.102 L4::lpc::Array_ref< ELEM_TYPE, LEN_TYPE > Struct Template Reference	1104
15.102.1 Detailed Description	1104
15.103 L4::lpc::As_value< T > Struct Template Reference	1105
15.103.1 Detailed Description	1105
15.104 L4::lpc::Call Struct Reference	1106
15.104.1 Detailed Description	1106
15.105 L4::lpc::Call_t< RIGHTS > Struct Template Reference	1107
15.105.1 Detailed Description	1108
15.106 L4::lpc::Call_zero_send_timeout Struct Reference	1108
15.106.1 Detailed Description	1109
15.107 L4::lpc::Cap< T > Class Template Reference	1109
15.107.1 Detailed Description	1112
15.107.2 Member Enumeration Documentation	1112
15.107.2.1 anonymous enum	1112
15.107.3 Constructor & Destructor Documentation	1113
15.107.3.1 Cap()	1113
15.107.4 Member Function Documentation	1113
15.107.4.1 from_ci()	1113
15.108 L4::lpc::Gen_fpage Class Reference	1113
15.108.1 Detailed Description	1115
15.108.2 Member Enumeration Documentation	1115
15.108.2.1 Type	1115
15.109 L4::lpc::In_out< T > Struct Template Reference	1116
15.109.1 Detailed Description	1116
15.110 L4::lpc::lostream Class Reference	1117
15.110.1 Detailed Description	1120



15.110.2 Constructor & Destructor Documentation	1121
15.110.2.1 lostream()	1121
15.110.3 Member Function Documentation	1121
15.110.3.1 call()	1121
15.110.3.2 get() [1/3]	1122
15.110.3.3 get() [2/3]	1123
15.110.3.4 get() [3/3]	1123
15.110.3.5 put() [1/2]	1124
15.110.3.6 put() [2/2]	1124
15.110.3.7 reply_and_wait() [1/2]	1124
15.110.3.8 reply_and_wait() [2/2]	1125
15.110.3.9 reset()	1126
15.111 L4::lpc::lstream Class Reference	1127
15.111.1 Detailed Description	1129
15.111.2 Constructor & Destructor Documentation	1130
15.111.2.1 lstream()	1130
15.111.3 Member Function Documentation	1131
15.111.3.1 get() [1/3]	1131
15.111.3.2 get() [2/3]	1131
15.111.3.3 get() [3/3]	1132
15.111.3.4 receive()	1133
15.111.3.5 reset()	1134
15.111.3.6 skip()	1135
15.111.3.7 tag() [1/2]	1135
15.111.3.8 tag() [2/2]	1136
15.111.3.9 wait() [1/2]	1136
15.111.3.10 wait() [2/2]	1137
15.112 L4::lpc::Msg::Clnt_val_ops< MTYPE, DIR, CLASS > Struct Template Reference	1138
15.112.1 Detailed Description	1139
15.113 L4::lpc::Msg::Cls_buffer Struct Reference	1139
15.113.1 Detailed Description	1140
15.114 L4::lpc::Msg::Cls_data Struct Reference	1141
15.114.1 Detailed Description	1141
15.115 L4::lpc::Msg::Cls_item Struct Reference	1142
15.115.1 Detailed Description	1142
15.116 L4::lpc::Msg::Dir_in Struct Reference	1143
15.116.1 Detailed Description	1143
15.117 L4::lpc::Msg::Dir_out Struct Reference	1144
15.117.1 Detailed Description	1144
15.118 L4::lpc::Msg::Do_in_data Struct Reference	1145
15.118.1 Detailed Description	1145
15.119 L4::lpc::Msg::Do_in_items Struct Reference	1146

15.119.1 Detailed Description . . . . .	1147
15.120 L4::lpc::Msg::Do_out_data Struct Reference . . . . .	1147
15.120.1 Detailed Description . . . . .	1148
15.121 L4::lpc::Msg::Do_out_items Struct Reference . . . . .	1148
15.121.1 Detailed Description . . . . .	1149
15.122 L4::lpc::Msg::Do_rcv_buffers Struct Reference . . . . .	1150
15.122.1 Detailed Description . . . . .	1151
15.123 L4::lpc::Msg::Elem< Array< A, LEN > & > Struct Template Reference . . . . .	1151
15.123.1 Detailed Description . . . . .	1151
15.124 L4::lpc::Msg::Elem< Array< A, LEN > > Struct Template Reference . . . . .	1152
15.124.1 Detailed Description . . . . .	1152
15.125 L4::lpc::Msg::Elem< Array_ref< A, LEN > & > Struct Template Reference . . . . .	1153
15.125.1 Detailed Description . . . . .	1153
15.126 L4::lpc::Msg::False Struct Reference . . . . .	1154
15.126.1 Detailed Description . . . . .	1155
15.127 L4::lpc::Msg::Is_valid_rpc_type< T > Struct Template Reference . . . . .	1156
15.127.1 Detailed Description . . . . .	1157
15.128 L4::lpc::Msg::Svr_arg_pack< IPC_TYPE > Struct Template Reference . . . . .	1158
15.128.1 Detailed Description . . . . .	1158
15.129 L4::lpc::Msg::Svr_val_ops< MTYPE, DIR, CLASS > Struct Template Reference . . . . .	1158
15.129.1 Detailed Description . . . . .	1159
15.130 L4::lpc::Msg::True Struct Reference . . . . .	1159
15.130.1 Detailed Description . . . . .	1161
15.131 L4::lpc::Msg_ptr< T > Class Template Reference . . . . .	1162
15.131.1 Detailed Description . . . . .	1162
15.131.2 Constructor & Destructor Documentation . . . . .	1163
15.131.2.1 Msg_ptr() . . . . .	1163
15.132 L4::lpc::Opt< T > Struct Template Reference . . . . .	1163
15.132.1 Detailed Description . . . . .	1165
15.133 L4::lpc::Ostream Class Reference . . . . .	1165
15.133.1 Detailed Description . . . . .	1168
15.133.2 Member Function Documentation . . . . .	1168
15.133.2.1 put() [1/2] . . . . .	1168
15.133.2.2 put() [2/2] . . . . .	1169
15.133.2.3 send() . . . . .	1169
15.133.2.4 tag() [1/2] . . . . .	1170
15.133.2.5 tag() [2/2] . . . . .	1170
15.134 L4::lpc::Out< T > Struct Template Reference . . . . .	1171
15.134.1 Detailed Description . . . . .	1172
15.135 L4::lpc::Rcv_fpage Class Reference . . . . .	1172
15.135.1 Detailed Description . . . . .	1175
15.135.2 Constructor & Destructor Documentation . . . . .	1175

15.135.2.1 Rcv_fpage()	1175
15.135.3 Member Function Documentation	1176
15.135.3.1 io()	1176
15.135.3.2 mem()	1177
15.135.3.3 obj()	1177
15.135.3.4 rcv_task()	1178
15.136 L4::lpc::Ret_array< T > Struct Template Reference	1179
15.136.1 Detailed Description	1180
15.137 L4::lpc::Send_only Struct Reference	1180
15.137.1 Detailed Description	1180
15.138 L4::lpc::Small_buf Class Reference	1181
15.138.1 Detailed Description	1181
15.138.2 Constructor & Destructor Documentation	1182
15.138.2.1 Small_buf() [1/2]	1182
15.138.2.2 Small_buf() [2/2]	1182
15.139 L4::lpc::Snd_fpage Class Reference	1183
15.139.1 Detailed Description	1186
15.139.2 Member Enumeration Documentation	1186
15.139.2.1 Cacheopt	1186
15.139.2.2 Continue	1187
15.139.2.3 Map_type	1187
15.139.3 Constructor & Destructor Documentation	1187
15.139.3.1 Snd_fpage() [1/2]	1187
15.139.3.2 Snd_fpage() [2/2]	1188
15.139.4 Member Function Documentation	1189
15.139.4.1 cap_received()	1189
15.139.4.2 id_received()	1189
15.139.4.3 io()	1189
15.139.4.4 is_compound()	1190
15.139.4.5 local_id_received()	1190
15.139.4.6 mem()	1191
15.139.4.7 obj()	1192
15.140 L4::lpc::Str_cp_in< T > Class Template Reference	1193
15.140.1 Detailed Description	1193
15.140.2 Constructor & Destructor Documentation	1194
15.140.2.1 Str_cp_in()	1194
15.141 L4::lpc::Varg Class Reference	1194
15.141.1 Detailed Description	1195
15.141.2 Member Function Documentation	1196
15.141.2.1 data()	1196
15.141.2.2 get_value()	1196
15.141.2.3 is_nil()	1197

15.141.2.4 is_of()	1197
15.141.2.5 is_of_int()	1198
15.141.2.6 length()	1199
15.141.2.7 tag()	1199
15.141.2.8 type()	1199
15.141.2.9 value()	1200
15.142 L4::lpc::Varg_list< MAX > Class Template Reference	1200
15.142.1 Detailed Description	1203
15.143 L4::lpc::Varg_list_ref Class Reference	1203
15.143.1 Detailed Description	1204
15.143.2 Constructor & Destructor Documentation	1205
15.143.2.1 Varg_list_ref()	1205
15.144 L4::lpc::Varg_list_ref::Iterator Class Reference	1205
15.144.1 Detailed Description	1206
15.145 L4::lpc_gate Class Reference	1207
15.145.1 Detailed Description	1210
15.145.2 Member Function Documentation	1211
15.145.2.1 get_infos()	1211
15.146 L4::lpc_svr::Br_manager_no_buffers Class Reference	1212
15.146.1 Detailed Description	1215
15.146.2 Member Function Documentation	1215
15.146.2.1 alloc_buffer_demand()	1215
15.147 L4::lpc_svr::Compound_reply Struct Reference	1216
15.147.1 Detailed Description	1218
15.148 L4::lpc_svr::Dbg_dispatch< R, Exc, Printer > Struct Template Reference	1218
15.148.1 Detailed Description	1220
15.149 L4::lpc_svr::Default_loop_hooks Struct Reference	1220
15.149.1 Detailed Description	1223
15.150 L4::lpc_svr::Default_setup_wait Struct Reference	1223
15.150.1 Detailed Description	1224
15.151 L4::lpc_svr::Default_timeout Struct Reference	1224
15.151.1 Detailed Description	1226
15.152 L4::lpc_svr::Direct_dispatch< R > Struct Template Reference	1226
15.152.1 Detailed Description	1227
15.153 L4::lpc_svr::Direct_dispatch< R * > Struct Template Reference	1228
15.153.1 Detailed Description	1229
15.154 L4::lpc_svr::Exc_dispatch< R, Exc > Struct Template Reference	1230
15.154.1 Detailed Description	1231
15.155 L4::lpc_svr::Ignore_errors Struct Reference	1232
15.155.1 Detailed Description	1233
15.156 L4::lpc_svr::Server_iface Class Reference	1233
15.156.1 Detailed Description	1236

15.156.2 Member Function Documentation . . . . .	1236
15.156.2.1 add_timeout() . . . . .	1236
15.156.2.2 alloc_buffer_demand() . . . . .	1236
15.156.2.3 get_rcv_cap() . . . . .	1237
15.156.2.4 rcv_cap() [1/2] . . . . .	1237
15.156.2.5 rcv_cap() [2/2] . . . . .	1238
15.156.2.6 realloc_rcv_cap() . . . . .	1239
15.156.2.7 remove_timeout() . . . . .	1240
15.157 L4::lpc_svr::Timeout Class Reference . . . . .	1240
15.157.1 Detailed Description . . . . .	1243
15.157.2 Member Function Documentation . . . . .	1243
15.157.2.1 expired() . . . . .	1243
15.157.2.2 timeout() . . . . .	1243
15.158 L4::lpc_svr::Timeout_queue Class Reference . . . . .	1244
15.158.1 Detailed Description . . . . .	1244
15.158.2 Member Function Documentation . . . . .	1245
15.158.2.1 add() . . . . .	1245
15.158.2.2 handle_expired_timeouts() . . . . .	1245
15.158.2.3 next_timeout() . . . . .	1246
15.158.2.4 remove() . . . . .	1246
15.158.2.5 timeout_expired() . . . . .	1247
15.159 L4::lpc_svr::Timeout_queue_hooks< HOOKS, BR_MAN > Class Template Reference . . . . .	1247
15.159.1 Detailed Description . . . . .	1251
15.159.2 Member Function Documentation . . . . .	1251
15.159.2.1 add_timeout() . . . . .	1251
15.159.2.2 remove_timeout() . . . . .	1252
15.160 L4::lrq Class Reference . . . . .	1252
15.160.1 Detailed Description . . . . .	1257
15.160.2 Member Function Documentation . . . . .	1258
15.160.2.1 bind_vcpu() . . . . .	1258
15.160.2.2 detach() . . . . .	1259
15.160.2.3 receive() . . . . .	1260
15.160.2.4 unmask() . . . . .	1261
15.160.2.5 wait() . . . . .	1262
15.161 L4::lrq_eoi Class Reference . . . . .	1262
15.161.1 Detailed Description . . . . .	1263
15.161.2 Member Function Documentation . . . . .	1264
15.161.2.1 unmask() . . . . .	1264
15.162 L4::lrq_handler_object Struct Reference . . . . .	1265
15.162.1 Detailed Description . . . . .	1268
15.163 L4::lrqep_t< Derived, BASE, bool > Struct Template Reference . . . . .	1269
15.163.1 Detailed Description . . . . .	1271

15.163.2 Member Function Documentation	1272
15.163.2.1 dispatch()	1272
15.163.2.2 obj_cap()	1273
15.164 L4::Kip::Mem_desc Class Reference	1273
15.164.1 Detailed Description	1275
15.164.2 Member Enumeration Documentation	1275
15.164.2.1 Arch_sub_type_common	1275
15.164.2.2 Info_sub_type	1276
15.164.2.3 Mem_type	1276
15.164.3 Constructor & Destructor Documentation	1277
15.164.3.1 Mem_desc()	1277
15.164.4 Member Function Documentation	1278
15.164.4.1 all() [1/2]	1278
15.164.4.2 all() [2/2]	1278
15.164.4.3 count() [1/2]	1279
15.164.4.4 count() [2/2]	1279
15.164.4.5 end()	1280
15.164.4.6 first()	1281
15.164.4.7 is_virtual()	1282
15.164.4.8 set()	1282
15.164.4.9 size()	1283
15.164.4.10 start()	1283
15.164.4.11 sub_type()	1284
15.164.4.12 type()	1284
15.165 L4::Kobject Class Reference	1284
15.165.1 Detailed Description	1285
15.165.2 Member Function Documentation	1285
15.165.2.1 cap()	1285
15.165.2.2 dec_refcnt()	1287
15.166 L4::Kobject_2t< Derived, Base1, Base2, PROTO, S_DEMAND > Class Template Reference	1288
15.166.1 Detailed Description	1290
15.166.2 Member Typedef Documentation	1290
15.166.2.1 __lface	1290
15.166.2.2 __lface_list	1291
15.166.2.3 Class	1291
15.166.3 Member Function Documentation	1291
15.166.3.1 __check_protocols__()	1291
15.166.3.2 c()	1291
15.167 L4::Kobject_3t< Derived, Base1, Base2, Base3, PROTO, S_DEMAND > Struct Template Reference	1292
15.167.1 Detailed Description	1293
15.167.2 Member Typedef Documentation	1294
15.167.2.1 __lface	1294

15.167.2.2 <code>__iface_list</code>	1294
15.167.2.3 Class	1294
15.167.3 Member Function Documentation	1295
15.167.3.1 <code>__check_protocols__()</code>	1295
15.167.3.2 <code>c()</code>	1295
15.168 L4::Kobject_demand< T > Struct Template Reference	1295
15.168.1 Detailed Description	1296
15.169 L4::Kobject_t< Derived, Base, PROTO, S_DEMAND > Class Template Reference	1296
15.169.1 Detailed Description	1297
15.170 L4::Kobject_typeid< T > Struct Template Reference	1298
15.170.1 Detailed Description	1299
15.170.2 Member Typedef Documentation	1299
15.170.2.1 Demand	1299
15.170.3 Member Function Documentation	1300
15.170.3.1 <code>demand()</code>	1300
15.170.3.2 <code>id()</code>	1300
15.170.3.3 <code>proto_dispatch()</code>	1301
15.171 L4::Kobject_typeid< void > Struct Reference	1302
15.171.1 Detailed Description	1303
15.171.2 Member Function Documentation	1303
15.171.2.1 <code>demand()</code>	1303
15.171.2.2 <code>id()</code>	1304
15.171.2.3 <code>proto_dispatch()</code>	1304
15.172 L4::Kobject_x< Derived, ARGS > Struct Template Reference	1305
15.172.1 Detailed Description	1306
15.173 L4::Lock_guard Class Reference	1306
15.173.1 Detailed Description	1307
15.173.2 Constructor & Destructor Documentation	1307
15.173.2.1 <code>Lock_guard()</code> [1/2]	1307
15.173.2.2 <code>Lock_guard()</code> [2/2]	1308
15.173.2.3 <code>~Lock_guard()</code>	1308
15.173.3 Member Function Documentation	1308
15.173.3.1 <code>operator=()</code>	1308
15.173.3.2 <code>status()</code>	1309
15.174 L4::Meta Class Reference	1309
15.174.1 Detailed Description	1312
15.174.2 Member Function Documentation	1313
15.174.2.1 <code>interface()</code>	1313
15.174.2.2 <code>num_interfaces()</code>	1313
15.174.2.3 <code>supports()</code>	1314
15.175 L4::Out_of_memory Class Reference	1315
15.175.1 Detailed Description	1318

15.176 L4::Pager Class Reference . . . . .	1319
15.176.1 Detailed Description . . . . .	1321
15.176.2 Member Function Documentation . . . . .	1321
15.176.2.1 page_fault() . . . . .	1321
15.177 L4::Platform_control Class Reference . . . . .	1322
15.177.1 Detailed Description . . . . .	1325
15.177.2 Member Function Documentation . . . . .	1326
15.177.2.1 cpu_allow_shutdown() . . . . .	1326
15.177.2.2 cpu_disable() . . . . .	1326
15.177.2.3 cpu_enable() . . . . .	1327
15.177.2.4 system_shutdown() . . . . .	1328
15.177.2.5 system_suspend() . . . . .	1329
15.178 L4::Poll_timeout_counter Class Reference . . . . .	1330
15.178.1 Detailed Description . . . . .	1331
15.178.2 Constructor & Destructor Documentation . . . . .	1332
15.178.2.1 Poll_timeout_counter() . . . . .	1332
15.178.3 Member Function Documentation . . . . .	1332
15.178.3.1 set() . . . . .	1332
15.178.3.2 timed_out() . . . . .	1333
15.179 L4::Poll_timeout_kipclock Class Reference . . . . .	1333
15.179.1 Detailed Description . . . . .	1334
15.179.2 Constructor & Destructor Documentation . . . . .	1334
15.179.2.1 Poll_timeout_kipclock() . . . . .	1334
15.179.3 Member Function Documentation . . . . .	1335
15.179.3.1 set() . . . . .	1335
15.179.3.2 test() . . . . .	1335
15.179.3.3 timed_out() . . . . .	1336
15.180 L4::Proto_t< P > Struct Template Reference . . . . .	1337
15.180.1 Detailed Description . . . . .	1337
15.181 L4::Rcv_endpoint Class Reference . . . . .	1337
15.181.1 Detailed Description . . . . .	1340
15.181.2 Member Function Documentation . . . . .	1341
15.181.2.1 bind_snd_destination() . . . . .	1341
15.181.2.2 bind_thread() . . . . .	1342
15.182 L4::Registry_iface Class Reference . . . . .	1343
15.182.1 Detailed Description . . . . .	1345
15.182.2 Member Function Documentation . . . . .	1345
15.182.2.1 register_irq_obj() . . . . .	1345
15.182.2.2 register_obj() [1/3] . . . . .	1346
15.182.2.3 register_obj() [2/3] . . . . .	1346
15.182.2.4 register_obj() [3/3] . . . . .	1347
15.182.2.5 unregister_obj() . . . . .	1347



15.183 L4::Runtime_error Class Reference . . . . .	1348
15.183.1 Detailed Description . . . . .	1350
15.183.2 Constructor & Destructor Documentation . . . . .	1350
15.183.2.1 Runtime_error() . . . . .	1350
15.183.3 Member Function Documentation . . . . .	1351
15.183.3.1 err_no() . . . . .	1351
15.183.3.2 extra_str() . . . . .	1352
15.184 L4::Scheduler Class Reference . . . . .	1352
15.184.1 Detailed Description . . . . .	1356
15.184.2 Member Function Documentation . . . . .	1357
15.184.2.1 idle_time() . . . . .	1357
15.184.2.2 info() . . . . .	1358
15.184.2.3 is_online() . . . . .	1358
15.184.2.4 run_thread() . . . . .	1359
15.185 L4::Semaphore Struct Reference . . . . .	1361
15.185.1 Detailed Description . . . . .	1364
15.185.2 Member Function Documentation . . . . .	1364
15.185.2.1 down() . . . . .	1364
15.185.2.2 up() . . . . .	1365
15.186 L4::Server< LOOP_HOOKS > Class Template Reference . . . . .	1366
15.186.1 Detailed Description . . . . .	1370
15.186.2 Constructor & Destructor Documentation . . . . .	1370
15.186.2.1 Server() . . . . .	1370
15.186.3 Member Function Documentation . . . . .	1370
15.186.3.1 internal_loop() . . . . .	1370
15.186.3.2 loop() . . . . .	1371
15.186.3.3 loop_dbg() . . . . .	1372
15.187 L4::Server_object Class Reference . . . . .	1372
15.187.1 Detailed Description . . . . .	1375
15.187.2 Member Function Documentation . . . . .	1375
15.187.2.1 dispatch() [1/2] . . . . .	1375
15.187.2.2 dispatch() [2/2] . . . . .	1376
15.188 L4::Server_object_t< IFACE, BASE > Struct Template Reference . . . . .	1377
15.188.1 Detailed Description . . . . .	1380
15.188.2 Member Function Documentation . . . . .	1381
15.188.2.1 dispatch_meta_request() . . . . .	1381
15.188.2.2 get_buffer_demand() . . . . .	1381
15.188.2.3 proto_dispatch() . . . . .	1381
15.189 L4::Server_object_x< Derived, IFACE, BASE > Struct Template Reference . . . . .	1382
15.189.1 Detailed Description . . . . .	1386
15.190 L4::Smart_cap< T, SMART > Class Template Reference . . . . .	1386
15.190.1 Detailed Description . . . . .	1390

15.190.2 Constructor & Destructor Documentation	1390
15.190.2.1 Smart_cap()	1390
15.191 L4::String Class Reference	1390
15.191.1 Detailed Description	1391
15.192 L4::Task Class Reference	1391
15.192.1 Detailed Description	1395
15.192.2 Member Function Documentation	1395
15.192.2.1 add_ku_mem()	1395
15.192.2.2 cap_equal()	1396
15.192.2.3 cap_valid()	1397
15.192.2.4 delete_obj()	1398
15.192.2.5 map()	1399
15.192.2.6 release_cap()	1400
15.192.2.7 unmap()	1401
15.192.2.8 unmap_batch()	1403
15.193 L4::Thread Class Reference	1404
15.193.1 Detailed Description	1407
15.193.2 Member Function Documentation	1407
15.193.2.1 control()	1407
15.193.2.2 ex_regs() [1/2]	1408
15.193.2.3 ex_regs() [2/2]	1409
15.193.2.4 modify_senders()	1410
15.193.2.5 register_del_irq()	1411
15.193.2.6 register_doorbell_irq()	1413
15.193.2.7 stats_time()	1414
15.193.2.8 switch_to()	1414
15.193.2.9 vcpu_control()	1415
15.193.2.10 vcpu_control_ext()	1416
15.193.2.11 vcpu_resume_commit()	1417
15.193.2.12 vcpu_resume_start()	1418
15.194 L4::Thread::Attr Class Reference	1419
15.194.1 Detailed Description	1420
15.194.2 Constructor & Destructor Documentation	1421
15.194.2.1 Attr()	1421
15.194.3 Member Function Documentation	1421
15.194.3.1 alien()	1421
15.194.3.2 bind()	1422
15.194.3.3 exc_handler() [1/2]	1422
15.194.3.4 exc_handler() [2/2]	1423
15.194.3.5 pager() [1/2]	1423
15.194.3.6 pager() [2/2]	1424
15.195 L4::Thread::Modify_senders Class Reference	1425

15.195.1 Detailed Description . . . . .	1425
15.195.2 Member Function Documentation . . . . .	1426
15.195.2.1 add() . . . . .	1426
15.196 L4::Thread_group Class Reference . . . . .	1427
15.196.1 Detailed Description . . . . .	1429
15.196.2 Member Function Documentation . . . . .	1429
15.196.2.1 add() . . . . .	1429
15.196.2.2 remove() . . . . .	1430
15.197 L4::Triggerable Struct Reference . . . . .	1431
15.197.1 Detailed Description . . . . .	1434
15.197.2 Member Function Documentation . . . . .	1434
15.197.2.1 trigger() . . . . .	1434
15.198 L4::Type_info Struct Reference . . . . .	1435
15.198.1 Detailed Description . . . . .	1436
15.199 L4::Type_info::Demand Class Reference . . . . .	1436
15.199.1 Detailed Description . . . . .	1438
15.199.2 Constructor & Destructor Documentation . . . . .	1439
15.199.2.1 Demand() . . . . .	1439
15.199.3 Member Function Documentation . . . . .	1439
15.199.3.1 no_demand() . . . . .	1439
15.200 L4::Type_info::Demand_t< CAPS, FLAGS, MEM, PORTS > Struct Template Reference . . . . .	1440
15.200.1 Detailed Description . . . . .	1443
15.200.2 Member Enumeration Documentation . . . . .	1443
15.200.2.1 anonymous enum . . . . .	1443
15.201 L4::Type_info::Demand_union_t< D1, D2 > Struct Template Reference . . . . .	1443
15.201.1 Detailed Description . . . . .	1446
15.202 L4::Typeid::Detail::_Rpc< OPCODE, O, X > Struct Template Reference . . . . .	1447
15.202.1 Detailed Description . . . . .	1447
15.203 L4::Typeid::Detail::_Rpc< OPCODE, O, Default_op< R > >::Rpc< Y > Struct Template Reference . . . . .	1448
15.203.1 Detailed Description . . . . .	1448
15.204 L4::Typeid::Detail::_Rpc< OPCODE, O, R, X... > Struct Template Reference . . . . .	1448
15.204.1 Detailed Description . . . . .	1451
15.205 L4::Typeid::Detail::_Rpc< OPCODE, O, R, X... >::Rpc< Y > Struct Template Reference . . . . .	1451
15.205.1 Detailed Description . . . . .	1451
15.206 L4::Typeid::Detail::Rpc_end Struct Reference . . . . .	1452
15.206.1 Detailed Description . . . . .	1452
15.207 L4::Typeid::P_dispatch< LIST > Struct Template Reference . . . . .	1452
15.207.1 Detailed Description . . . . .	1453
15.208 L4::Typeid::Raw_ipc< CLASS > Struct Template Reference . . . . .	1453
15.208.1 Detailed Description . . . . .	1454
15.209 L4::Typeid::Rpc_nocode< OPERATION > Struct Template Reference . . . . .	1455
15.209.1 Detailed Description . . . . .	1456

15.210 L4::Typeid::Rpc< RPCS > Struct Template Reference . . . . .	1457
15.210.1 Detailed Description . . . . .	1458
15.211 L4::Typeid::Rpc_code< OPCODE_TYPE > Struct Template Reference . . . . .	1459
15.211.1 Detailed Description . . . . .	1460
15.212 L4::Typeid::Rpc_code< OPCODE_TYPE >::F< RPCS > Struct Template Reference . . . . .	1460
15.212.1 Detailed Description . . . . .	1462
15.213 L4::Typeid::Rpc_sys< ARG > Struct Template Reference . . . . .	1463
15.213.1 Detailed Description . . . . .	1464
15.214 L4::Types::__Add_rvalue_reference_helper< T, typename > Struct Template Reference . . . . .	1465
15.214.1 Detailed Description . . . . .	1466
15.215 L4::Types::__Add_rvalue_reference_helper< T, Void< T && > > Struct Template Reference . . . . .	1466
15.215.1 Detailed Description . . . . .	1468
15.216 L4::Types::__Underlying_type_helper< T, bool > Struct Template Reference . . . . .	1468
15.216.1 Detailed Description . . . . .	1469
15.217 L4::Types::__Underlying_type_helper< T, false > Struct Template Reference . . . . .	1469
15.217.1 Detailed Description . . . . .	1471
15.218 L4::Types::Add_rvalue_reference< T > Struct Template Reference . . . . .	1471
15.218.1 Detailed Description . . . . .	1471
15.219 L4::Types::Bool< V > Struct Template Reference . . . . .	1472
15.219.1 Detailed Description . . . . .	1472
15.220 L4::Types::False Struct Reference . . . . .	1473
15.220.1 Detailed Description . . . . .	1475
15.221 L4::Types::Flags< BITS_ENUM, UNDERLYING > Class Template Reference . . . . .	1476
15.221.1 Detailed Description . . . . .	1478
15.221.2 Member Enumeration Documentation . . . . .	1479
15.221.2.1 None_type . . . . .	1479
15.221.3 Constructor & Destructor Documentation . . . . .	1479
15.221.3.1 Flags() [1/2] . . . . .	1479
15.221.3.2 Flags() [2/2] . . . . .	1479
15.221.4 Member Function Documentation . . . . .	1480
15.221.4.1 clear() . . . . .	1480
15.221.4.2 from_raw() . . . . .	1480
15.222 L4::Types::Flags_ops_t< DT > Struct Template Reference . . . . .	1480
15.222.1 Detailed Description . . . . .	1483
15.223 L4::Types::Flags_t< DT, T > Struct Template Reference . . . . .	1483
15.223.1 Detailed Description . . . . .	1486
15.224 L4::Types::Int_for_size< SIZE, bool > Struct Template Reference . . . . .	1487
15.224.1 Detailed Description . . . . .	1487
15.225 L4::Types::Int_for_type< T > Struct Template Reference . . . . .	1488
15.225.1 Detailed Description . . . . .	1488
15.226 L4::Types::Integral_constant< T, Value > Struct Template Reference . . . . .	1489
15.226.1 Detailed Description . . . . .	1489

15.227 L4::Types::Is_enum< T > Struct Template Reference . . . . .	1490
15.227.1 Detailed Description . . . . .	1491
15.228 L4::Types::Same< A, B > Struct Template Reference . . . . .	1492
15.228.1 Detailed Description . . . . .	1493
15.229 L4::Types::True Struct Reference . . . . .	1494
15.229.1 Detailed Description . . . . .	1496
15.230 L4::Types::Underlying_type< T > Struct Template Reference . . . . .	1497
15.230.1 Detailed Description . . . . .	1498
15.231 L4::Uart Class Reference . . . . .	1498
15.231.1 Detailed Description . . . . .	1501
15.231.2 Member Function Documentation . . . . .	1501
15.231.2.1 change_mode() . . . . .	1501
15.231.2.2 char_avail() . . . . .	1501
15.231.2.3 enable_rx_irq() . . . . .	1502
15.231.2.4 generic_write() . . . . .	1502
15.231.2.5 get_char() . . . . .	1503
15.231.2.6 mode() . . . . .	1503
15.231.2.7 rate() . . . . .	1503
15.231.2.8 shutdown() . . . . .	1503
15.231.2.9 startup() . . . . .	1504
15.231.2.10 write() . . . . .	1504
15.232 L4::Uart_apb Class Reference . . . . .	1505
15.232.1 Detailed Description . . . . .	1507
15.232.2 Member Function Documentation . . . . .	1507
15.232.2.1 change_mode() . . . . .	1507
15.232.2.2 char_avail() . . . . .	1508
15.232.2.3 enable_rx_irq() . . . . .	1508
15.232.2.4 get_char() . . . . .	1509
15.232.2.5 shutdown() . . . . .	1509
15.232.2.6 startup() . . . . .	1509
15.232.2.7 write() . . . . .	1510
15.233 L4::Unknown_error Class Reference . . . . .	1510
15.233.1 Detailed Description . . . . .	1513
15.234 L4::Vcon Class Reference . . . . .	1513
15.234.1 Detailed Description . . . . .	1517
15.234.2 Member Function Documentation . . . . .	1518
15.234.2.1 get_attr() . . . . .	1518
15.234.2.2 read() . . . . .	1518
15.234.2.3 read_with_flags() . . . . .	1519
15.234.2.4 send() . . . . .	1520
15.234.2.5 set_attr() . . . . .	1521
15.234.2.6 write() . . . . .	1522

15.235 L4::Vm Class Reference . . . . .	1523
15.235.1 Detailed Description . . . . .	1527
15.236 l4_buf_regs_t Struct Reference . . . . .	1527
15.236.1 Detailed Description . . . . .	1528
15.237 l4_exc_regs_t Struct Reference . . . . .	1528
15.237.1 Detailed Description . . . . .	1530
15.237.2 Field Documentation . . . . .	1530
15.237.2.1 flags . . . . .	1530
15.237.2.2 ss . . . . .	1531
15.238 l4_fpage_t Union Reference . . . . .	1531
15.238.1 Detailed Description . . . . .	1531
15.239 l4_icu_info_t Struct Reference . . . . .	1532
15.239.1 Detailed Description . . . . .	1533
15.239.2 Field Documentation . . . . .	1533
15.239.2.1 features . . . . .	1533
15.240 l4_icu_msi_info_t Struct Reference . . . . .	1533
15.240.1 Detailed Description . . . . .	1534
15.241 l4_kernel_info_mem_desc_t Struct Reference . . . . .	1534
15.241.1 Detailed Description . . . . .	1534
15.242 l4_kernel_info_t Struct Reference . . . . .	1535
15.242.1 Detailed Description . . . . .	1536
15.243 l4_msg_regs_t Union Reference . . . . .	1536
15.243.1 Detailed Description . . . . .	1537
15.244 l4_msgtag_t Struct Reference . . . . .	1537
15.244.1 Detailed Description . . . . .	1538
15.244.2 Member Function Documentation . . . . .	1539
15.244.2.1 flags() . . . . .	1539
15.244.2.2 has_error() . . . . .	1539
15.245 l4_sched_cpu_set_t Struct Reference . . . . .	1540
15.245.1 Detailed Description . . . . .	1541
15.245.2 Member Function Documentation . . . . .	1541
15.245.2.1 granularity() . . . . .	1541
15.245.2.2 offset() . . . . .	1542
15.245.2.3 set() . . . . .	1542
15.245.3 Field Documentation . . . . .	1543
15.245.3.1 gran_offset . . . . .	1543
15.246 l4_sched_param_t Struct Reference . . . . .	1544
15.246.1 Detailed Description . . . . .	1544
15.246.2 Field Documentation . . . . .	1545
15.246.2.1 prio . . . . .	1545
15.247 l4_snd_fpage_t Struct Reference . . . . .	1545
15.247.1 Detailed Description . . . . .	1546

15.248 <a href="#">l4_thread_regs_t</a> Struct Reference	1546
15.248.1 Detailed Description	1546
15.248.2 Field Documentation	1547
15.248.2.1 error	1547
15.248.2.2 free_marker	1547
15.249 <a href="#">l4_timeout_s</a> Struct Reference	1547
15.249.1 Detailed Description	1548
15.250 <a href="#">l4_timeout_t</a> Union Reference	1548
15.250.1 Detailed Description	1549
15.251 <a href="#">l4_vcon_attr_t</a> Struct Reference	1549
15.251.1 Detailed Description	1550
15.251.2 Member Function Documentation	1550
15.251.2.1 set_raw()	1550
15.252 <a href="#">l4_vcpu_arch_state_t</a> Struct Reference	1551
15.252.1 Detailed Description	1551
15.253 <a href="#">l4_vcpu_ipc_regs_t</a> Struct Reference	1551
15.253.1 Detailed Description	1552
15.254 <a href="#">l4_vcpu_regs_t</a> Struct Reference	1553
15.254.1 Detailed Description	1554
15.254.2 Field Documentation	1555
15.254.2.1 ax	1555
15.254.2.2 bp	1555
15.254.2.3 bx	1555
15.254.2.4 cx	1555
15.254.2.5 di	1555
15.254.2.6 dx	1556
15.254.2.7 si	1556
15.255 <a href="#">l4_vcpu_state_t</a> Struct Reference	1556
15.255.1 Detailed Description	1559
15.255.2 Field Documentation	1559
15.255.2.1 version	1559
15.256 <a href="#">l4_vm_svm_vmcb_control_area</a> Struct Reference	1560
15.256.1 Detailed Description	1560
15.257 <a href="#">l4_vm_svm_vmcb_state_save_area</a> Struct Reference	1560
15.257.1 Detailed Description	1561
15.258 <a href="#">l4_vm_svm_vmcb_state_save_area_seg</a> Struct Reference	1562
15.258.1 Detailed Description	1562
15.259 <a href="#">l4_vm_svm_vmcb_t</a> Struct Reference	1562
15.259.1 Detailed Description	1563
15.260 <a href="#">l4_vm_tz_state</a> Struct Reference	1564
15.260.1 Detailed Description	1564
15.261 <a href="#">l4_vm_vmx_vcpu_infos_t</a> Struct Reference	1564

15.261.1 Detailed Description . . . . .	1565
15.261.2 Field Documentation . . . . .	1565
15.261.2.1 df1 . . . . .	1565
15.262 l4_vm_vmx_vcpu_state_t Struct Reference . . . . .	1565
15.262.1 Detailed Description . . . . .	1566
15.263 l4_vm_vmx_vcpu_vmcs_t Struct Reference . . . . .	1567
15.263.1 Detailed Description . . . . .	1568
15.264 l4_vmx_offset_table_t Struct Reference . . . . .	1568
15.264.1 Detailed Description . . . . .	1569
15.265 L4drivers::Mmio_register_block< MAX_BITS > Struct Template Reference . . . . .	1570
15.265.1 Detailed Description . . . . .	1571
15.266 L4drivers::Register_block< MAX_BITS, BLOCK > Class Template Reference . . . . .	1572
15.266.1 Detailed Description . . . . .	1572
15.266.2 Member Function Documentation . . . . .	1573
15.266.2.1 operator[]() [1/2] . . . . .	1573
15.266.2.2 operator[]() [2/2] . . . . .	1574
15.266.2.3 r() [1/2] . . . . .	1575
15.266.2.4 r() [2/2] . . . . .	1575
15.267 L4drivers::Register_block_base< MAX_BITS > Struct Template Reference . . . . .	1576
15.267.1 Detailed Description . . . . .	1577
15.268 L4drivers::Register_block_impl< BASE, MAX_BITS > Struct Template Reference . . . . .	1577
15.268.1 Detailed Description . . . . .	1579
15.269 L4drivers::Register_block_tmpl< BLOCK > Class Template Reference . . . . .	1579
15.269.1 Detailed Description . . . . .	1580
15.270 L4drivers::Register_tmpl< BITS, BLOCK > Class Template Reference . . . . .	1580
15.270.1 Detailed Description . . . . .	1583
15.270.2 Member Function Documentation . . . . .	1583
15.270.2.1 clear() . . . . .	1583
15.270.2.2 modify() . . . . .	1584
15.270.2.3 operator=() . . . . .	1584
15.270.2.4 set() . . . . .	1585
15.270.2.5 write() . . . . .	1585
15.271 L4drivers::Ro_register_block< MAX_BITS, BLOCK > Class Template Reference . . . . .	1586
15.271.1 Detailed Description . . . . .	1587
15.271.2 Member Function Documentation . . . . .	1587
15.271.2.1 operator[]() . . . . .	1587
15.271.2.2 r() . . . . .	1588
15.272 L4drivers::Ro_register_tmpl< BITS, BLOCK > Class Template Reference . . . . .	1588
15.272.1 Detailed Description . . . . .	1590
15.272.2 Member Function Documentation . . . . .	1590
15.272.2.1 operator value_type() . . . . .	1590
15.272.2.2 read() . . . . .	1590



15.273 L4Re::Cap_alloc Class Reference . . . . .	1591
15.273.1 Detailed Description . . . . .	1592
15.273.2 Member Function Documentation . . . . .	1592
15.273.2.1 alloc() [1/2] . . . . .	1592
15.273.2.2 alloc() [2/2] . . . . .	1593
15.273.2.3 free() . . . . .	1594
15.274 L4Re::Console Class Reference . . . . .	1594
15.274.1 Detailed Description . . . . .	1597
15.275 L4Re::Core::Ref_ptr< T, CNT > Class Template Reference . . . . .	1597
15.275.1 Detailed Description . . . . .	1599
15.275.2 Constructor & Destructor Documentation . . . . .	1600
15.275.2.1 Ref_ptr() [1/3] . . . . .	1600
15.275.2.2 Ref_ptr() [2/3] . . . . .	1600
15.275.2.3 Ref_ptr() [3/3] . . . . .	1601
15.275.3 Member Function Documentation . . . . .	1601
15.275.3.1 get() . . . . .	1601
15.275.3.2 ptr() . . . . .	1601
15.275.3.3 release() . . . . .	1601
15.276 L4Re::Dataspace Class Reference . . . . .	1602
15.276.1 Detailed Description . . . . .	1605
15.276.2 Member Function Documentation . . . . .	1605
15.276.2.1 allocate() . . . . .	1605
15.276.2.2 clear() . . . . .	1606
15.276.2.3 copy_in() . . . . .	1607
15.276.2.4 flags() . . . . .	1608
15.276.2.5 info() . . . . .	1609
15.276.2.6 map() . . . . .	1610
15.276.2.7 map_info() . . . . .	1612
15.276.2.8 map_region() . . . . .	1613
15.276.2.9 size() . . . . .	1614
15.277 L4Re::Dataspace::F Struct Reference . . . . .	1615
15.277.1 Detailed Description . . . . .	1615
15.277.2 Member Enumeration Documentation . . . . .	1615
15.277.2.1 anonymous enum . . . . .	1615
15.277.2.2 Flags . . . . .	1616
15.278 L4Re::Dataspace::Stats Struct Reference . . . . .	1616
15.278.1 Detailed Description . . . . .	1617
15.279 L4Re::Debug_obj Class Reference . . . . .	1617
15.279.1 Detailed Description . . . . .	1620
15.279.2 Member Function Documentation . . . . .	1620
15.279.2.1 debug() . . . . .	1620
15.280 L4Re::Default_event_payload Struct Reference . . . . .	1621

15.280.1 Detailed Description . . . . .	1622
15.281 L4Re::Dma_space Class Reference . . . . .	1622
15.281.1 Detailed Description . . . . .	1624
15.281.2 Member Typedef Documentation . . . . .	1624
15.281.2.1 Attributes . . . . .	1624
15.281.3 Member Enumeration Documentation . . . . .	1624
15.281.3.1 Attribute . . . . .	1624
15.281.3.2 Direction . . . . .	1625
15.281.3.3 Space_attrib . . . . .	1625
15.281.4 Member Function Documentation . . . . .	1626
15.281.4.1 associate() . . . . .	1626
15.281.4.2 disassociate() . . . . .	1627
15.281.4.3 map() . . . . .	1627
15.281.4.4 unmap() . . . . .	1628
15.282 L4Re::Env Class Reference . . . . .	1629
15.282.1 Detailed Description . . . . .	1632
15.282.2 Member Function Documentation . . . . .	1633
15.282.2.1 dbg_events() [1/2] . . . . .	1633
15.282.2.2 dbg_events() [2/2] . . . . .	1633
15.282.2.3 env() . . . . .	1634
15.282.2.4 factory() [1/2] . . . . .	1635
15.282.2.5 factory() [2/2] . . . . .	1635
15.282.2.6 first_free_cap() [1/2] . . . . .	1635
15.282.2.7 first_free_cap() [2/2] . . . . .	1636
15.282.2.8 first_free_utcb() [1/2] . . . . .	1636
15.282.2.9 first_free_utcb() [2/2] . . . . .	1636
15.282.2.10 get() . . . . .	1637
15.282.2.11 get_cap() [1/2] . . . . .	1638
15.282.2.12 get_cap() [2/2] . . . . .	1638
15.282.2.13 initial_caps() [1/2] . . . . .	1639
15.282.2.14 initial_caps() [2/2] . . . . .	1640
15.282.2.15 itas() [1/2] . . . . .	1640
15.282.2.16 itas() [2/2] . . . . .	1640
15.282.2.17 log() [1/2] . . . . .	1640
15.282.2.18 log() [2/2] . . . . .	1641
15.282.2.19 main_thread() [1/2] . . . . .	1641
15.282.2.20 main_thread() [2/2] . . . . .	1641
15.282.2.21 mem_alloc() [1/2] . . . . .	1641
15.282.2.22 mem_alloc() [2/2] . . . . .	1642
15.282.2.23 parent() [1/2] . . . . .	1642
15.282.2.24 parent() [2/2] . . . . .	1642
15.282.2.25 rm() [1/2] . . . . .	1642

15.282.2.26 rm() [2/2]	1643
15.282.2.27 scheduler() [1/2]	1643
15.282.2.28 scheduler() [2/2]	1643
15.282.2.29 task()	1643
15.282.2.30 utcb_area() [1/2]	1644
15.282.2.31 utcb_area() [2/2]	1644
15.283 L4Re::Event Class Reference	1644
15.283.1 Detailed Description	1648
15.283.2 Member Function Documentation	1648
15.283.2.1 get_axis_info()	1648
15.283.2.2 get_buffer()	1650
15.283.2.3 get_num_streams()	1651
15.283.2.4 get_stream_info()	1651
15.283.2.5 get_stream_info_for_id()	1652
15.283.2.6 get_stream_state_for_id()	1653
15.284 L4Re::Event_buffer_t< PAYLOAD > Class Template Reference	1654
15.284.1 Detailed Description	1656
15.284.2 Constructor & Destructor Documentation	1657
15.284.2.1 Event_buffer_t()	1657
15.284.3 Member Function Documentation	1657
15.284.3.1 next()	1657
15.284.3.2 put()	1657
15.285 L4Re::Event_buffer_t< PAYLOAD >::Event Struct Reference	1658
15.285.1 Detailed Description	1658
15.286 L4Re::Inhibitor Class Reference	1659
15.286.1 Detailed Description	1661
15.286.2 Member Enumeration Documentation	1662
15.286.2.1 anonymous enum	1662
15.286.3 Member Function Documentation	1662
15.286.3.1 acquire()	1662
15.286.3.2 next_lock_info()	1663
15.286.3.3 release()	1664
15.287 L4Re::Itas Class Reference	1665
15.287.1 Detailed Description	1668
15.287.2 Member Enumeration Documentation	1668
15.287.2.1 anonymous enum	1668
15.287.3 Member Function Documentation	1668
15.287.3.1 getitimer()	1668
15.287.3.2 raise()	1669
15.287.3.3 register_thread()	1670
15.287.3.4 setitimer()	1670
15.287.3.5 sigaction()	1671

15.287.3.6 sigaltstack()	1672
15.287.3.7 sigpending()	1673
15.287.3.8 sigprocmask()	1673
15.287.3.9 unregister_thread()	1674
15.288 L4Re::Log Class Reference	1675
15.288.1 Detailed Description	1680
15.288.2 Member Function Documentation	1680
15.288.2.1 print()	1680
15.288.2.2 printn()	1680
15.289 L4Re::Mem_alloc Class Reference	1681
15.289.1 Detailed Description	1684
15.289.2 Member Enumeration Documentation	1685
15.289.2.1 Mem_alloc_flags	1685
15.289.3 Member Function Documentation	1685
15.289.3.1 alloc()	1685
15.289.3.2 info()	1686
15.290 L4Re::Mem_alloc::Stats Struct Reference	1687
15.290.1 Detailed Description	1688
15.290.2 Field Documentation	1688
15.290.2.1 mem_free	1688
15.290.2.2 mem_limit	1688
15.290.2.3 mem_used	1689
15.290.2.4 quota	1689
15.290.2.5 quota_used	1689
15.291 L4Re::Mmio_space Struct Reference	1690
15.291.1 Detailed Description	1692
15.291.2 Member Enumeration Documentation	1693
15.291.2.1 Access_width	1693
15.291.3 Member Function Documentation	1693
15.291.3.1 mmio_read()	1693
15.291.3.2 mmio_write()	1694
15.292 L4Re::Namespace Class Reference	1695
15.292.1 Detailed Description	1699
15.292.2 Member Enumeration Documentation	1699
15.292.2.1 Query_result_flags	1699
15.292.2.2 Query_timeout	1699
15.292.2.3 Register_flags	1700
15.292.3 Member Function Documentation	1700
15.292.3.1 query() [1/2]	1700
15.292.3.2 query() [2/2]	1701
15.292.3.3 register_obj()	1702
15.292.3.4 unlink()	1704

15.293 L4Re::Ned::Cmd_control Class Reference . . . . .	1705
15.293.1 Detailed Description . . . . .	1705
15.293.2 Member Function Documentation . . . . .	1706
15.293.2.1 execute() [1/2] . . . . .	1706
15.293.2.2 execute() [2/2] . . . . .	1706
15.294 L4Re::Parent Class Reference . . . . .	1707
15.294.1 Detailed Description . . . . .	1710
15.294.2 Member Function Documentation . . . . .	1710
15.294.2.1 signal() . . . . .	1710
15.295 L4Re::Random Struct Reference . . . . .	1712
15.295.1 Detailed Description . . . . .	1715
15.295.2 Member Function Documentation . . . . .	1715
15.295.2.1 get_random() . . . . .	1715
15.296 L4Re::Rm Class Reference . . . . .	1716
15.296.1 Detailed Description . . . . .	1721
15.296.2 Member Enumeration Documentation . . . . .	1721
15.296.2.1 Detach_flags . . . . .	1721
15.296.2.2 Detach_result . . . . .	1722
15.296.2.3 Region_flag_shifts . . . . .	1722
15.296.3 Member Function Documentation . . . . .	1722
15.296.3.1 attach() [1/2] . . . . .	1722
15.296.3.2 attach() [2/2] . . . . .	1724
15.296.3.3 detach() [1/3] . . . . .	1726
15.296.3.4 detach() [2/3] . . . . .	1727
15.296.3.5 detach() [3/3] . . . . .	1728
15.296.3.6 find() . . . . .	1729
15.296.3.7 free_area() . . . . .	1730
15.296.3.8 get_areas() . . . . .	1731
15.296.3.9 get_info() . . . . .	1732
15.296.3.10 get_regions() . . . . .	1733
15.296.3.11 reserve_area() [1/2] . . . . .	1735
15.296.3.12 reserve_area() [2/2] . . . . .	1736
15.297 L4Re::Rm::Area Struct Reference . . . . .	1737
15.297.1 Detailed Description . . . . .	1737
15.298 L4Re::Rm::F Struct Reference . . . . .	1737
15.298.1 Detailed Description . . . . .	1738
15.298.2 Member Enumeration Documentation . . . . .	1738
15.298.2.1 Attach_flags . . . . .	1738
15.298.2.2 Region_flags . . . . .	1739
15.299 L4Re::Rm::Region Struct Reference . . . . .	1739
15.299.1 Detailed Description . . . . .	1740
15.300 L4Re::Rm::Unique_region< T > Class Template Reference . . . . .	1740

15.300.1 Detailed Description . . . . .	1742
15.300.2 Constructor & Destructor Documentation . . . . .	1742
15.300.2.1 Unique_region() [1/3] . . . . .	1742
15.300.2.2 Unique_region() [2/3] . . . . .	1743
15.300.2.3 Unique_region() [3/3] . . . . .	1743
15.300.2.4 ~Unique_region() . . . . .	1743
15.300.3 Member Function Documentation . . . . .	1744
15.300.3.1 get() . . . . .	1744
15.300.3.2 is_valid() . . . . .	1744
15.300.3.3 operator=() . . . . .	1745
15.300.3.4 release() . . . . .	1745
15.300.3.5 reset() . . . . .	1745
15.301 L4Re::Smart_cap_auto< Unmap_flags > Class Template Reference . . . . .	1746
15.301.1 Detailed Description . . . . .	1746
15.302 L4Re::Smart_count_cap< Unmap_flags > Class Template Reference . . . . .	1746
15.302.1 Detailed Description . . . . .	1747
15.303 L4Re::Util::_Cap_alloc Class Reference . . . . .	1748
15.303.1 Detailed Description . . . . .	1749
15.303.2 Member Function Documentation . . . . .	1750
15.303.2.1 alloc() [1/2] . . . . .	1750
15.303.2.2 alloc() [2/2] . . . . .	1750
15.303.2.3 free() . . . . .	1751
15.304 L4Re::Util::Bitmap< BITS > Class Template Reference . . . . .	1751
15.304.1 Detailed Description . . . . .	1755
15.304.2 Member Function Documentation . . . . .	1755
15.304.2.1 scan_zero() . . . . .	1755
15.305 L4Re::Util::Bitmap_base Class Reference . . . . .	1756
15.305.1 Detailed Description . . . . .	1758
15.305.2 Member Enumeration Documentation . . . . .	1759
15.305.2.1 anonymous enum . . . . .	1759
15.305.3 Member Function Documentation . . . . .	1759
15.305.3.1 atomic_clear_bit() . . . . .	1759
15.305.3.2 atomic_get_and_clear() . . . . .	1759
15.305.3.3 atomic_get_and_set() . . . . .	1760
15.305.3.4 atomic_set_bit() . . . . .	1760
15.305.3.5 bit() [1/2] . . . . .	1760
15.305.3.6 bit() [2/2] . . . . .	1761
15.305.3.7 bit_index() . . . . .	1761
15.305.3.8 clear_bit() . . . . .	1761
15.305.3.9 operator[]() [1/2] . . . . .	1762
15.305.3.10 operator[]() [2/2] . . . . .	1762
15.305.3.11 scan_zero() . . . . .	1762

15.305.3.12 set_bit()	1763
15.305.3.13 word_index()	1763
15.306 L4Re::Util::Bitmap_base::Bit Class Reference	1764
15.306.1 Detailed Description	1764
15.307 L4Re::Util::Bitmap_base::Char< BITS > Class Template Reference	1764
15.307.1 Detailed Description	1765
15.308 L4Re::Util::Bitmap_base::Word< BITS > Class Template Reference	1765
15.308.1 Detailed Description	1766
15.309 L4Re::Util::Br_manager Class Reference	1766
15.309.1 Detailed Description	1769
15.309.2 Member Function Documentation	1770
15.309.2.1 alloc_buffer_demand()	1770
15.309.2.2 get_rcv_cap()	1770
15.309.2.3 realloc_rcv_cap()	1771
15.309.2.4 set_rcv_cap_flags()	1771
15.310 L4Re::Util::Br_manager_hooks Struct Reference	1772
15.310.1 Detailed Description	1774
15.311 L4Re::Util::Br_manager_timeout_hooks Struct Reference	1774
15.311.1 Detailed Description	1777
15.312 L4Re::Util::Cap_alloc_base Class Reference	1778
15.312.1 Detailed Description	1778
15.313 L4Re::Util::Counter< COUNTER > Struct Template Reference	1779
15.313.1 Detailed Description	1779
15.313.2 Member Function Documentation	1779
15.313.2.1 dec()	1779
15.313.2.2 inc()	1780
15.314 L4Re::Util::Counter_atomic< COUNTER > Struct Template Reference	1780
15.314.1 Detailed Description	1781
15.314.2 Member Function Documentation	1781
15.314.2.1 dec()	1781
15.314.2.2 inc()	1781
15.315 L4Re::Util::Counting_cap_alloc< COUNTERTYPE, Dbg > Class Template Reference	1782
15.315.1 Detailed Description	1783
15.315.2 Constructor & Destructor Documentation	1783
15.315.2.1 Counting_cap_alloc()	1783
15.315.3 Member Function Documentation	1784
15.315.3.1 alloc() [1/2]	1784
15.315.3.2 alloc() [2/2]	1784
15.315.3.3 free()	1785
15.315.3.4 release()	1786
15.315.3.5 setup()	1787
15.315.3.6 take()	1787

15.316 L4Re::Util::Dataspace_svr Class Reference	1788
15.316.1 Detailed Description	1789
15.316.2 Member Function Documentation	1789
15.316.2.1 allocate()	1789
15.316.2.2 clear()	1790
15.316.2.3 copy()	1790
15.316.2.4 is_static()	1791
15.316.2.5 map()	1791
15.316.2.6 map_hook()	1792
15.316.2.7 map_info()	1793
15.316.2.8 page_shift()	1794
15.316.2.9 release()	1794
15.316.2.10 take()	1794
15.317 L4Re::Util::Event_buffer_consumer_t< PAYLOAD > Class Template Reference	1795
15.317.1 Detailed Description	1797
15.317.2 Member Function Documentation	1797
15.317.2.1 foreach_available_event()	1797
15.317.2.2 process()	1798
15.318 L4Re::Util::Event_buffer_t< PAYLOAD > Class Template Reference	1798
15.318.1 Detailed Description	1801
15.318.2 Member Function Documentation	1801
15.318.2.1 attach()	1801
15.318.2.2 buf()	1801
15.318.2.3 detach()	1802
15.319 L4Re::Util::Event_svr< SVR > Class Template Reference	1802
15.319.1 Detailed Description	1804
15.320 L4Re::Util::Event_t< PAYLOAD > Class Template Reference	1804
15.320.1 Detailed Description	1805
15.320.2 Member Enumeration Documentation	1806
15.320.2.1 Mode	1806
15.320.3 Member Function Documentation	1806
15.320.3.1 buffer()	1806
15.320.3.2 init()	1806
15.320.3.3 init_poll()	1807
15.320.3.4 irq()	1807
15.321 L4Re::Util::Item_alloc_base Class Reference	1808
15.321.1 Detailed Description	1808
15.322 L4Re::Util::Names::Name Class Reference	1809
15.322.1 Detailed Description	1812
15.323 L4Re::Util::Names::Name_space Class Reference	1812
15.323.1 Detailed Description	1813
15.323.2 Member Function Documentation	1813



15.323.2.1 alloc_dynamic_entry()	1813
15.323.2.2 copy_receive_cap()	1814
15.323.2.3 free_capability()	1814
15.323.2.4 free_dynamic_entry()	1815
15.323.2.5 free_epiface()	1815
15.323.2.6 get_epiface()	1816
15.324 L4Re::Util::Object_registry Class Reference	1817
15.324.1 Detailed Description	1820
15.324.2 Constructor & Destructor Documentation	1820
15.324.2.1 Object_registry() [1/2]	1820
15.324.2.2 Object_registry() [2/2]	1821
15.324.3 Member Function Documentation	1821
15.324.3.1 register_irq_obj()	1821
15.324.3.2 register_obj() [1/3]	1822
15.324.3.3 register_obj() [2/3]	1822
15.324.3.4 register_obj() [3/3]	1823
15.324.3.5 unregister_obj()	1823
15.325 L4Re::Util::Ref_cap< T > Struct Template Reference	1824
15.325.1 Detailed Description	1825
15.326 L4Re::Util::Ref_del_cap< T > Struct Template Reference	1826
15.326.1 Detailed Description	1826
15.327 L4Re::Util::Registry_server< LOOP_HOOKS > Class Template Reference	1827
15.327.1 Detailed Description	1830
15.327.2 Constructor & Destructor Documentation	1830
15.327.2.1 Registry_server() [1/3]	1830
15.327.2.2 Registry_server() [2/3]	1831
15.327.2.3 Registry_server() [3/3]	1831
15.327.3 Member Function Documentation	1831
15.327.3.1 loop()	1831
15.327.3.2 loop_dbg()	1832
15.328 L4Re::Util::Smart_cap_auto< Unmap_flags > Class Template Reference	1833
15.328.1 Detailed Description	1834
15.329 L4Re::Util::Smart_count_cap< Unmap_flags > Class Template Reference	1834
15.329.1 Detailed Description	1835
15.330 L4Re::Util::Vcon_svr< SVR > Class Template Reference	1835
15.330.1 Detailed Description	1836
15.331 L4Re::Util::Video::Goos_svr Class Reference	1836
15.331.1 Detailed Description	1838
15.331.2 Member Function Documentation	1838
15.331.2.1 get_fb()	1838
15.331.2.2 init_infos()	1838
15.331.2.3 refresh()	1839

15.331.2.4 screen_info()	1839
15.331.2.5 view_info()	1839
15.332 L4Re::Vfs::Be_file Class Reference	1840
15.332.1 Detailed Description	1843
15.332.2 Member Function Documentation	1843
15.332.2.1 check_ready()	1843
15.332.2.2 data_space()	1843
15.332.2.3 fstat()	1844
15.332.2.4 unlock_all_locks()	1844
15.333 L4Re::Vfs::Be_file_system Class Reference	1845
15.333.1 Detailed Description	1846
15.333.2 Constructor & Destructor Documentation	1847
15.333.2.1 Be_file_system()	1847
15.333.2.2 ~Be_file_system()	1847
15.333.3 Member Function Documentation	1847
15.333.3.1 type()	1847
15.334 L4Re::Vfs::Directory Class Reference	1848
15.334.1 Detailed Description	1849
15.334.2 Member Function Documentation	1850
15.334.2.1 faccessat()	1850
15.334.2.2 link()	1850
15.334.2.3 mkdir()	1851
15.334.2.4 rename()	1851
15.334.2.5 rmdir()	1852
15.334.2.6 symlink()	1852
15.334.2.7 unlink()	1853
15.335 L4Re::Vfs::File Class Reference	1853
15.335.1 Detailed Description	1856
15.336 L4Re::Vfs::File_system Class Reference	1857
15.336.1 Detailed Description	1858
15.336.2 Member Function Documentation	1858
15.336.2.1 mount()	1858
15.336.2.2 type()	1859
15.337 L4Re::Vfs::Fs Class Reference	1859
15.337.1 Detailed Description	1862
15.337.2 Member Function Documentation	1862
15.337.2.1 alloc_fd()	1862
15.337.2.2 free_fd()	1862
15.337.2.3 get_file()	1863
15.337.2.4 mount()	1863
15.337.2.5 set_fd()	1864
15.338 L4Re::Vfs::Generic_file Class Reference	1864

15.338.1 Detailed Description . . . . .	1866
15.338.2 Member Enumeration Documentation . . . . .	1867
15.338.2.1 Ready_type . . . . .	1867
15.338.3 Member Function Documentation . . . . .	1867
15.338.3.1 check_ready() . . . . .	1867
15.338.3.2 fchmod() . . . . .	1868
15.338.3.3 fstat() . . . . .	1869
15.338.3.4 get_status_flags() . . . . .	1870
15.338.3.5 set_status_flags() . . . . .	1871
15.338.3.6 unlock_all_locks() . . . . .	1872
15.339 L4Re::Vfs::Mman Class Reference . . . . .	1873
15.339.1 Detailed Description . . . . .	1874
15.340 L4Re::Vfs::Ops Class Reference . . . . .	1874
15.340.1 Detailed Description . . . . .	1877
15.341 L4Re::Vfs::Regular_file Class Reference . . . . .	1877
15.341.1 Detailed Description . . . . .	1879
15.341.2 Member Function Documentation . . . . .	1880
15.341.2.1 data_space() . . . . .	1880
15.341.2.2 fdatsync() . . . . .	1880
15.341.2.3 fsync() . . . . .	1881
15.341.2.4 ftruncate() . . . . .	1881
15.341.2.5 get_lock() . . . . .	1882
15.341.2.6 lseek() . . . . .	1883
15.341.2.7 readv() . . . . .	1884
15.341.2.8 set_lock() . . . . .	1885
15.341.2.9 writev() . . . . .	1886
15.342 L4Re::Vfs::Special_file Class Reference . . . . .	1887
15.342.1 Detailed Description . . . . .	1889
15.342.2 Member Function Documentation . . . . .	1889
15.342.2.1 ioctl() . . . . .	1889
15.343 L4Re::Video::Color_component Class Reference . . . . .	1890
15.343.1 Detailed Description . . . . .	1891
15.343.2 Constructor & Destructor Documentation . . . . .	1891
15.343.2.1 Color_component() . . . . .	1891
15.343.3 Member Function Documentation . . . . .	1891
15.343.3.1 dump() . . . . .	1891
15.343.3.2 get() . . . . .	1892
15.343.3.3 operator==( ) . . . . .	1892
15.343.3.4 set() . . . . .	1893
15.343.3.5 shift() . . . . .	1893
15.343.3.6 size() . . . . .	1894
15.344 L4Re::Video::Goos Class Reference . . . . .	1895

15.344.1 Detailed Description . . . . .	1898
15.344.2 Member Enumeration Documentation . . . . .	1898
15.344.2.1 Flags . . . . .	1898
15.344.3 Member Function Documentation . . . . .	1899
15.344.3.1 create_buffer() . . . . .	1899
15.344.3.2 create_view() . . . . .	1899
15.344.3.3 delete_buffer() . . . . .	1900
15.344.3.4 delete_view() . . . . .	1901
15.344.3.5 get_static_buffer() . . . . .	1902
15.344.3.6 info() . . . . .	1903
15.344.3.7 view() . . . . .	1904
15.345 L4Re::Video::Goos::Info Struct Reference . . . . .	1905
15.345.1 Detailed Description . . . . .	1907
15.346 L4Re::Video::Pixel_info Class Reference . . . . .	1907
15.346.1 Detailed Description . . . . .	1908
15.346.2 Constructor & Destructor Documentation . . . . .	1909
15.346.2.1 Pixel_info() [1/2] . . . . .	1909
15.346.2.2 Pixel_info() [2/2] . . . . .	1910
15.346.3 Member Function Documentation . . . . .	1911
15.346.3.1 a() [1/2] . . . . .	1911
15.346.3.2 a() [2/2] . . . . .	1911
15.346.3.3 b() [1/2] . . . . .	1912
15.346.3.4 b() [2/2] . . . . .	1912
15.346.3.5 bits_per_pixel() . . . . .	1913
15.346.3.6 bytes_per_pixel() [1/2] . . . . .	1913
15.346.3.7 bytes_per_pixel() [2/2] . . . . .	1914
15.346.3.8 dump() . . . . .	1914
15.346.3.9 g() [1/2] . . . . .	1915
15.346.3.10 g() [2/2] . . . . .	1915
15.346.3.11 has_alpha() . . . . .	1915
15.346.3.12 operator==( ) . . . . .	1916
15.346.3.13 padding() . . . . .	1916
15.346.3.14 r() [1/2] . . . . .	1917
15.346.3.15 r() [2/2] . . . . .	1917
15.347 L4Re::Video::View Class Reference . . . . .	1918
15.347.1 Detailed Description . . . . .	1919
15.347.2 Member Enumeration Documentation . . . . .	1919
15.347.2.1 Flags . . . . .	1919
15.347.2.2 V_flags . . . . .	1920
15.347.3 Member Function Documentation . . . . .	1920
15.347.3.1 info() . . . . .	1920
15.347.3.2 refresh() . . . . .	1921

15.347.3.3 set_info()	1922
15.347.3.4 set_viewport()	1923
15.347.3.5 stack()	1924
15.348 L4Re::Video::View::Info Struct Reference	1925
15.348.1 Detailed Description	1926
15.349 l4re_aux_t Struct Reference	1927
15.349.1 Detailed Description	1927
15.350 l4re_ds_stats_t Struct Reference	1928
15.350.1 Detailed Description	1928
15.351 l4re_elf_aux_mword_t Struct Reference	1928
15.351.1 Detailed Description	1929
15.352 l4re_elf_aux_t Struct Reference	1929
15.352.1 Detailed Description	1929
15.353 l4re_elf_aux_vma_t Struct Reference	1930
15.353.1 Detailed Description	1930
15.354 l4re_env_cap_entry_t Struct Reference	1930
15.354.1 Detailed Description	1931
15.354.2 Constructor & Destructor Documentation	1931
15.354.2.1 l4re_env_cap_entry_t()	1931
15.354.3 Field Documentation	1932
15.354.3.1 flags	1932
15.355 l4re_env_t Struct Reference	1932
15.355.1 Detailed Description	1934
15.355.2 Field Documentation	1934
15.355.2.1 caps	1934
15.356 l4re_event_t Struct Reference	1935
15.356.1 Detailed Description	1935
15.357 l4re_video_color_component_t Struct Reference	1936
15.357.1 Detailed Description	1936
15.358 l4re_video_goos_info_t Struct Reference	1936
15.358.1 Detailed Description	1938
15.359 l4re_video_pixel_info_t Struct Reference	1938
15.359.1 Detailed Description	1939
15.360 l4re_video_view_info_t Struct Reference	1939
15.360.1 Detailed Description	1941
15.361 l4re_video_view_t Struct Reference	1941
15.361.1 Detailed Description	1941
15.362 l4shmc_ringbuf_head_t Struct Reference	1942
15.362.1 Detailed Description	1942
15.363 l4shmc_ringbuf_t Struct Reference	1943
15.363.1 Detailed Description	1944
15.364 l4util_l4mod_info Struct Reference	1944

15.364.1 Detailed Description . . . . .	1945
15.364.2 Field Documentation . . . . .	1945
15.364.2.1 vbe_ctrl_info . . . . .	1945
15.365 l4util_l4mod_mod Struct Reference . . . . .	1946
15.365.1 Detailed Description . . . . .	1946
15.366 l4util_mb_addr_range_t Struct Reference . . . . .	1947
15.366.1 Detailed Description . . . . .	1947
15.367 l4util_mb_apm_t Struct Reference . . . . .	1948
15.367.1 Detailed Description . . . . .	1948
15.368 l4util_mb_drive_t Struct Reference . . . . .	1948
15.368.1 Detailed Description . . . . .	1949
15.369 l4util_mb_info_t Struct Reference . . . . .	1949
15.369.1 Detailed Description . . . . .	1950
15.370 l4util_mb_mod_t Struct Reference . . . . .	1951
15.370.1 Detailed Description . . . . .	1951
15.371 l4util_mb_vbe_ctrl_t Struct Reference . . . . .	1952
15.371.1 Detailed Description . . . . .	1952
15.372 l4util_mb_vbe_mode_t Struct Reference . . . . .	1952
15.372.1 Detailed Description . . . . .	1955
15.373 L4vbus::Device Class Reference . . . . .	1956
15.373.1 Detailed Description . . . . .	1958
15.373.2 Constructor & Destructor Documentation . . . . .	1959
15.373.2.1 Device() . . . . .	1959
15.373.3 Member Function Documentation . . . . .	1959
15.373.3.1 bus_cap() . . . . .	1959
15.373.3.2 dev_handle() . . . . .	1960
15.373.3.3 device() . . . . .	1961
15.373.3.4 device_by_hid() . . . . .	1961
15.373.3.5 get_resource() . . . . .	1962
15.373.3.6 is_compatible() . . . . .	1963
15.373.3.7 next_device() . . . . .	1964
15.373.3.8 operator!=(()) . . . . .	1965
15.373.3.9 operator==(()) . . . . .	1965
15.374 L4vbus::Gpio_module Class Reference . . . . .	1966
15.374.1 Detailed Description . . . . .	1969
15.374.2 Member Function Documentation . . . . .	1969
15.374.2.1 config_pad() . . . . .	1969
15.374.2.2 get() . . . . .	1970
15.374.2.3 pin() . . . . .	1970
15.374.2.4 set() . . . . .	1971
15.374.2.5 setup() . . . . .	1972
15.375 L4vbus::Gpio_module::Pin_slice Struct Reference . . . . .	1973

15.375.1 Detailed Description . . . . .	1973
15.376 L4vbus::Gpio_pin Class Reference . . . . .	1973
15.376.1 Detailed Description . . . . .	1977
15.376.2 Member Function Documentation . . . . .	1977
15.376.2.1 config_get() . . . . .	1977
15.376.2.2 config_pad() . . . . .	1978
15.376.2.3 config_pull() . . . . .	1978
15.376.2.4 get() . . . . .	1979
15.376.2.5 pin() . . . . .	1979
15.376.2.6 set() . . . . .	1980
15.376.2.7 setup() . . . . .	1980
15.376.2.8 to_irq() . . . . .	1981
15.377 L4vbus::Icu Class Reference . . . . .	1982
15.377.1 Detailed Description . . . . .	1985
15.377.2 Member Enumeration Documentation . . . . .	1985
15.377.2.1 Src_types . . . . .	1985
15.377.3 Member Function Documentation . . . . .	1985
15.377.3.1 vicu() . . . . .	1985
15.378 L4vbus::Pci_dev Class Reference . . . . .	1986
15.378.1 Detailed Description . . . . .	1989
15.378.2 Member Function Documentation . . . . .	1990
15.378.2.1 cfg_read() . . . . .	1990
15.378.2.2 cfg_write() . . . . .	1990
15.378.2.3 irq_enable() . . . . .	1991
15.379 L4vbus::Pci_host_bridge Class Reference . . . . .	1992
15.379.1 Detailed Description . . . . .	1996
15.379.2 Member Function Documentation . . . . .	1996
15.379.2.1 cfg_read() . . . . .	1996
15.379.2.2 cfg_write() . . . . .	1997
15.379.2.3 irq_enable() . . . . .	1997
15.380 L4vbus::Pm< DEC > Class Template Reference . . . . .	1998
15.380.1 Detailed Description . . . . .	2000
15.380.2 Member Function Documentation . . . . .	2000
15.380.2.1 pm_resume() . . . . .	2000
15.380.2.2 pm_suspend() . . . . .	2001
15.381 L4vbus::Vbus Class Reference . . . . .	2001
15.381.1 Detailed Description . . . . .	2008
15.381.2 Member Function Documentation . . . . .	2008
15.381.2.1 assign_dma_domain() [1/2] . . . . .	2008
15.381.2.2 assign_dma_domain() [2/2] . . . . .	2009
15.381.2.3 release_ioport() . . . . .	2010
15.381.2.4 request_ioport() . . . . .	2011

15.381.2.5 root()	2011
15.382 l4vbus_device_t Struct Reference	2012
15.382.1 Detailed Description	2013
15.383 l4vbus_resource_t Struct Reference	2013
15.383.1 Detailed Description	2014
15.384 L4vcpu::State Class Reference	2014
15.384.1 Detailed Description	2015
15.384.2 Constructor & Destructor Documentation	2015
15.384.2.1 State()	2015
15.384.3 Member Function Documentation	2015
15.384.3.1 add()	2015
15.384.3.2 clear()	2016
15.384.3.3 set()	2016
15.385 L4vcpu::Vcpu Class Reference	2016
15.385.1 Detailed Description	2020
15.385.2 Member Function Documentation	2020
15.385.2.1 cast() [1/2]	2020
15.385.2.2 cast() [2/2]	2020
15.385.2.3 entry_ip()	2021
15.385.2.4 entry_sp()	2022
15.385.2.5 ext_alloc()	2022
15.385.2.6 i() [1/2]	2023
15.385.2.7 i() [2/2]	2023
15.385.2.8 irq_disable_save()	2023
15.385.2.9 irq_enable()	2024
15.385.2.10 irq_restore()	2024
15.385.2.11 is_irq_entry()	2025
15.385.2.12 is_page_fault_entry()	2025
15.385.2.13 r() [1/2]	2026
15.385.2.14 r() [2/2]	2026
15.385.2.15 saved_state() [1/2]	2026
15.385.2.16 saved_state() [2/2]	2027
15.385.2.17 state() [1/2]	2027
15.385.2.18 state() [2/2]	2027
15.385.2.19 task()	2028
15.385.2.20 wait_for_event()	2028
15.386 L4virtio::Device Class Reference	2029
15.386.1 Detailed Description	2033
15.386.2 Member Function Documentation	2034
15.386.2.1 config_queue()	2034
15.386.2.2 device_config()	2035
15.386.2.3 device_notification_irq()	2035



15.386.2.4 register_ds()	2036
15.386.2.5 set_status()	2037
15.387 L4virtio::Driver::Block_device Class Reference	2039
15.387.1 Detailed Description	2042
15.387.2 Member Function Documentation	2042
15.387.2.1 add_block()	2042
15.387.2.2 process_request()	2043
15.387.2.3 process_used_queue()	2043
15.387.2.4 send_request()	2044
15.387.2.5 setup_device()	2045
15.387.2.6 start_request()	2046
15.388 L4virtio::Driver::Block_device::Handle Class Reference	2047
15.388.1 Detailed Description	2047
15.389 L4virtio::Driver::Device Class Reference	2047
15.389.1 Detailed Description	2050
15.389.2 Member Function Documentation	2050
15.389.2.1 bind_notification_irq()	2050
15.389.2.2 config_queue()	2051
15.389.2.3 driver_acknowledge()	2052
15.389.2.4 driver_connect()	2052
15.389.2.5 feature_negotiated()	2054
15.389.2.6 max_queue_size()	2055
15.389.2.7 register_ds()	2055
15.389.2.8 send()	2056
15.389.2.9 send_and_wait()	2057
15.389.2.10 wait()	2058
15.389.2.11 wait_for_next_used()	2059
15.390 L4virtio::Driver::Virtio_net_device Class Reference	2060
15.390.1 Detailed Description	2064
15.390.2 Member Function Documentation	2064
15.390.2.1 bind_rx_notification_irq()	2064
15.390.2.2 finish_rx()	2064
15.390.2.3 rx_pkt()	2065
15.390.2.4 rx_queue_size()	2065
15.390.2.5 setup_device()	2066
15.390.2.6 tx()	2067
15.390.2.7 tx_queue_size()	2067
15.390.2.8 wait_rx()	2068
15.391 L4virtio::Driver::Virtio_net_device::Packet Struct Reference	2069
15.391.1 Detailed Description	2069
15.392 L4virtio::Driver::Virtqueue Class Reference	2070
15.392.1 Detailed Description	2073

15.392.2 Member Function Documentation . . . . .	2074
15.392.2.1 alloc_descriptor() . . . . .	2074
15.392.2.2 desc() . . . . .	2074
15.392.2.3 enqueue_descriptor() . . . . .	2075
15.392.2.4 find_next_used() . . . . .	2075
15.392.2.5 free_descriptor() . . . . .	2076
15.392.2.6 init_queue() [1/2] . . . . .	2076
15.392.2.7 init_queue() [2/2] . . . . .	2077
15.392.2.8 initialize_rings() . . . . .	2077
15.393 L4virtio::Ptr< T > Class Template Reference . . . . .	2079
15.393.1 Detailed Description . . . . .	2080
15.393.2 Member Enumeration Documentation . . . . .	2080
15.393.2.1 Invalid_type . . . . .	2080
15.393.3 Member Function Documentation . . . . .	2081
15.393.3.1 get() . . . . .	2081
15.393.3.2 is_valid() . . . . .	2081
15.394 L4virtio::Svr::Bad_descriptor Struct Reference . . . . .	2082
15.394.1 Detailed Description . . . . .	2083
15.394.2 Member Enumeration Documentation . . . . .	2083
15.394.2.1 Error . . . . .	2083
15.394.3 Constructor & Destructor Documentation . . . . .	2083
15.394.3.1 Bad_descriptor() . . . . .	2083
15.394.4 Member Function Documentation . . . . .	2084
15.394.4.1 message() . . . . .	2084
15.395 L4virtio::Svr::Block_dev_base< Ds_data > Class Template Reference . . . . .	2084
15.395.1 Detailed Description . . . . .	2088
15.395.2 Constructor & Destructor Documentation . . . . .	2088
15.395.2.1 Block_dev_base() . . . . .	2088
15.395.3 Member Function Documentation . . . . .	2089
15.395.3.1 finalize_request() . . . . .	2089
15.395.3.2 get_writeback() . . . . .	2090
15.395.3.3 set_blk_size() . . . . .	2090
15.395.3.4 set_config_wce() . . . . .	2091
15.395.3.5 set_discard() . . . . .	2091
15.395.3.6 set_size_max() . . . . .	2091
15.395.3.7 set_topology() . . . . .	2092
15.395.3.8 set_write_zeroes() . . . . .	2092
15.396 L4virtio::Svr::Block_request< Ds_data > Class Template Reference . . . . .	2093
15.396.1 Detailed Description . . . . .	2093
15.396.2 Member Function Documentation . . . . .	2094
15.396.2.1 data_size() . . . . .	2094
15.396.2.2 next_block() . . . . .	2094

15.397 L4virtio::Svr::Console::Control_message Struct Reference . . . . .	2095
15.397.1 Detailed Description . . . . .	2096
15.397.2 Member Enumeration Documentation . . . . .	2096
15.397.2.1 Events . . . . .	2096
15.398 L4virtio::Svr::Console::Control_request Struct Reference . . . . .	2097
15.398.1 Detailed Description . . . . .	2098
15.399 L4virtio::Svr::Console::Device Class Reference . . . . .	2098
15.399.1 Detailed Description . . . . .	2103
15.399.2 Constructor & Destructor Documentation . . . . .	2103
15.399.2.1 Device() [1/3] . . . . .	2103
15.399.2.2 Device() [2/3] . . . . .	2104
15.399.2.3 Device() [3/3] . . . . .	2105
15.399.3 Member Function Documentation . . . . .	2105
15.399.3.1 notify_queue() . . . . .	2105
15.399.3.2 port() . . . . .	2106
15.399.3.3 port_read() . . . . .	2107
15.399.3.4 port_write() . . . . .	2108
15.399.3.5 process_device_ready() . . . . .	2110
15.399.3.6 process_port_open() . . . . .	2111
15.399.3.7 process_port_ready() . . . . .	2111
15.400 L4virtio::Svr::Console::Device_port Struct Reference . . . . .	2112
15.400.1 Detailed Description . . . . .	2116
15.401 L4virtio::Svr::Console::Features Struct Reference . . . . .	2116
15.401.1 Detailed Description . . . . .	2119
15.401.2 Member Typedef Documentation . . . . .	2120
15.401.2.1 console_multiport_bfm_t . . . . .	2120
15.401.2.2 console_size_bfm_t . . . . .	2120
15.401.2.3 emerg_write_bfm_t . . . . .	2120
15.402 L4virtio::Svr::Console::Port Struct Reference . . . . .	2121
15.402.1 Detailed Description . . . . .	2124
15.402.2 Member Enumeration Documentation . . . . .	2124
15.402.2.1 Port_status . . . . .	2124
15.402.3 Field Documentation . . . . .	2125
15.402.3.1 state_transitions . . . . .	2125
15.403 L4virtio::Svr::Console::Port::Transition Struct Reference . . . . .	2125
15.403.1 Detailed Description . . . . .	2126
15.404 L4virtio::Svr::Console::Virtio_con Class Reference . . . . .	2126
15.404.1 Detailed Description . . . . .	2130
15.404.2 Constructor & Destructor Documentation . . . . .	2131
15.404.2.1 Virtio_con() . . . . .	2131
15.404.3 Member Function Documentation . . . . .	2132
15.404.3.1 handle_control_message() . . . . .	2132

15.404.3.2 notify_queue()	2133
15.404.3.3 port()	2133
15.404.3.4 port_add()	2134
15.404.3.5 port_name()	2135
15.404.3.6 port_open()	2136
15.404.3.7 port_remove()	2137
15.404.3.8 process_device_ready()	2138
15.404.3.9 process_port_open()	2139
15.404.3.10 process_port_ready()	2140
15.404.3.11 reset_device()	2141
15.404.3.12 send_control_message()	2141
15.405 L4virtio::Svr::Data_buffer Struct Reference	2143
15.405.1 Detailed Description	2144
15.405.2 Constructor & Destructor Documentation	2144
15.405.2.1 Data_buffer()	2144
15.405.3 Member Function Documentation	2145
15.405.3.1 copy_to()	2145
15.405.3.2 done()	2146
15.405.3.3 set()	2146
15.405.3.4 skip()	2146
15.406 L4virtio::Svr::Dev_config Class Reference	2147
15.406.1 Detailed Description	2149
15.406.2 Constructor & Destructor Documentation	2149
15.406.2.1 Dev_config() [1/2]	2149
15.406.2.2 Dev_config() [2/2]	2150
15.406.3 Member Function Documentation	2151
15.406.3.1 add_irq_status()	2151
15.406.3.2 change_queue_config()	2152
15.406.3.3 ds()	2152
15.406.3.4 get_cmd()	2153
15.406.3.5 guest_features()	2153
15.406.3.6 hdr()	2154
15.406.3.7 negotiated_features()	2154
15.406.3.8 qconfig()	2155
15.406.3.9 reset_cmd()	2156
15.406.3.10 reset_queue()	2156
15.406.3.11 set_device_needs_reset()	2157
15.406.3.12 set_device_notify_index()	2158
15.406.3.13 set_status()	2158
15.406.3.14 status()	2159
15.407 L4virtio::Svr::Dev_features Struct Reference	2159
15.407.1 Detailed Description	2162

15.408 L4virtio::Svr::Dev_status Struct Reference . . . . .	2162
15.408.1 Detailed Description . . . . .	2165
15.408.2 Member Function Documentation . . . . .	2165
15.408.2.1 running() . . . . .	2165
15.409 L4virtio::Svr::Device_t< DATA > Class Template Reference . . . . .	2165
15.409.1 Detailed Description . . . . .	2168
15.409.2 Member Function Documentation . . . . .	2169
15.409.2.1 add_trusted_dataspaces() . . . . .	2169
15.409.2.2 device_error() . . . . .	2169
15.409.2.3 device_notify_irq() . . . . .	2169
15.409.2.4 handle_mem_cmd_write() . . . . .	2170
15.409.2.5 init_mem_info() . . . . .	2170
15.409.2.6 register_driver_irq() . . . . .	2170
15.409.2.7 reset_queue_config() . . . . .	2171
15.409.2.8 setup_queue() . . . . .	2171
15.410 L4virtio::Svr::Driver_mem_list_t< DATA > Class Template Reference . . . . .	2172
15.410.1 Detailed Description . . . . .	2174
15.410.2 Member Function Documentation . . . . .	2174
15.410.2.1 add() . . . . .	2174
15.410.2.2 find() . . . . .	2175
15.410.2.3 full() . . . . .	2175
15.410.2.4 init() . . . . .	2176
15.410.2.5 load_desc() [ 1 / 3 ] . . . . .	2176
15.410.2.6 load_desc() [ 2 / 3 ] . . . . .	2177
15.410.2.7 load_desc() [ 3 / 3 ] . . . . .	2177
15.410.2.8 remove() . . . . .	2178
15.411 L4virtio::Svr::Driver_mem_region_t< DATA > Class Template Reference . . . . .	2178
15.411.1 Detailed Description . . . . .	2181
15.411.2 Constructor & Destructor Documentation . . . . .	2181
15.411.2.1 Driver_mem_region_t() . . . . .	2181
15.411.3 Member Function Documentation . . . . .	2181
15.411.3.1 contains() . . . . .	2181
15.411.3.2 drv_base() . . . . .	2182
15.411.3.3 ds() . . . . .	2182
15.411.3.4 ds_offset() . . . . .	2182
15.411.3.5 empty() . . . . .	2183
15.411.3.6 flags() . . . . .	2183
15.411.3.7 is_writable() . . . . .	2183
15.411.3.8 local() . . . . .	2183
15.411.3.9 local_base() . . . . .	2184
15.411.3.10 size() . . . . .	2184
15.412 L4virtio::Svr::Request_processor Class Reference . . . . .	2185

15.412.1 Detailed Description . . . . .	2186
15.412.2 Member Function Documentation . . . . .	2186
15.412.2.1 current_flags() . . . . .	2186
15.412.2.2 has_more() . . . . .	2187
15.412.2.3 next() . . . . .	2188
15.412.2.4 start() [1/2] . . . . .	2189
15.412.2.5 start() [2/2] . . . . .	2191
15.413 L4virtio::Svr::Scmi::Base_attr_t Struct Reference . . . . .	2192
15.413.1 Detailed Description . . . . .	2193
15.414 L4virtio::Svr::Scmi::Base_proto Class Reference . . . . .	2193
15.414.1 Detailed Description . . . . .	2195
15.415 L4virtio::Svr::Scmi::Perf_proto Class Reference . . . . .	2195
15.415.1 Detailed Description . . . . .	2197
15.416 L4virtio::Svr::Scmi::Performance_attr_t Struct Reference . . . . .	2198
15.416.1 Detailed Description . . . . .	2198
15.417 L4virtio::Svr::Scmi::Performance_describe_level_t Struct Reference . . . . .	2199
15.417.1 Detailed Description . . . . .	2199
15.418 L4virtio::Svr::Scmi::Performance_describe_levels_n_t Struct Reference . . . . .	2199
15.418.1 Detailed Description . . . . .	2200
15.419 L4virtio::Svr::Scmi::Performance_domain_attr_t Struct Reference . . . . .	2201
15.419.1 Detailed Description . . . . .	2202
15.420 L4virtio::Svr::Scmi::Proto< OBSERV > Struct Template Reference . . . . .	2203
15.420.1 Detailed Description . . . . .	2204
15.421 L4virtio::Svr::Scmi::Scmi_dev Class Reference . . . . .	2204
15.421.1 Detailed Description . . . . .	2207
15.422 L4virtio::Svr::Scmi::Scmi_hdr_t Struct Reference . . . . .	2208
15.422.1 Detailed Description . . . . .	2209
15.423 L4virtio::Svr::Virtio_gpio< Request_handler, Epiface > Class Template Reference . . . . .	2210
15.423.1 Detailed Description . . . . .	2214
15.424 L4virtio::Svr::Virtio_gpio< Request_handler, Epiface >::Host_irq Struct Reference . . . . .	2214
15.424.1 Detailed Description . . . . .	2217
15.425 L4virtio::Svr::Virtio_gpio< Request_handler, Epiface >::Irq_handler Struct Reference . . . . .	2218
15.425.1 Detailed Description . . . . .	2218
15.426 L4virtio::Svr::Virtio_gpio< Request_handler, Epiface >::Request_processor Struct Reference . . . . .	2219
15.426.1 Detailed Description . . . . .	2221
15.426.2 Member Function Documentation . . . . .	2221
15.426.2.1 get_request() . . . . .	2221
15.427 L4virtio::Svr::Virtio_i2c< Request_handler, Epiface > Class Template Reference . . . . .	2222
15.427.1 Detailed Description . . . . .	2226
15.428 L4virtio::Svr::Virtio_i2c< Request_handler, Epiface >::Host_irq Class Reference . . . . .	2226
15.428.1 Detailed Description . . . . .	2229
15.429 L4virtio::Svr::Virtio_i2c< Request_handler, Epiface >::Request_processor Class Reference . . . . .	2230

15.429.1 Detailed Description . . . . .	2232
15.429.2 Member Function Documentation . . . . .	2232
15.429.2.1 get_request() . . . . .	2232
15.430 L4virtio::Svr::Virtio_rng< Rnd_state, Epiface > Class Template Reference . . . . .	2233
15.430.1 Detailed Description . . . . .	2237
15.431 L4virtio::Svr::Virtio_rng< Rnd_state, Epiface >::Host_irq Class Reference . . . . .	2237
15.431.1 Detailed Description . . . . .	2240
15.432 L4virtio::Svr::Virtio_rng< Rnd_state, Epiface >::Request_processor Class Reference . . . . .	2241
15.432.1 Detailed Description . . . . .	2243
15.433 L4virtio::Svr::Virtio_spi< Spi_request_handler, Epiface > Class Template Reference . . . . .	2243
15.433.1 Detailed Description . . . . .	2248
15.434 L4virtio::Svr::Virtio_spi< Spi_request_handler, Epiface >::Host_irq Class Reference . . . . .	2248
15.434.1 Detailed Description . . . . .	2251
15.435 L4virtio::Svr::Virtio_spi< Spi_request_handler, Epiface >::Request_processor Class Reference . . . . .	2252
15.435.1 Detailed Description . . . . .	2254
15.435.2 Member Function Documentation . . . . .	2254
15.435.2.1 get_request() . . . . .	2254
15.436 L4virtio::Svr::Virtqueue Class Reference . . . . .	2255
15.436.1 Detailed Description . . . . .	2258
15.436.2 Member Function Documentation . . . . .	2259
15.436.2.1 consumed() [1/2] . . . . .	2259
15.436.2.2 consumed() [2/2] . . . . .	2260
15.436.2.3 desc() . . . . .	2260
15.436.2.4 desc_avail() . . . . .	2261
15.436.2.5 disable_notify() . . . . .	2262
15.436.2.6 enable_notify() . . . . .	2263
15.436.2.7 finish() [1/2] . . . . .	2263
15.436.2.8 finish() [2/2] . . . . .	2265
15.436.2.9 next_avail() . . . . .	2266
15.436.2.10 rewind_avail() . . . . .	2267
15.437 L4virtio::Svr::Virtqueue::Head_desc Class Reference . . . . .	2267
15.437.1 Detailed Description . . . . .	2268
15.437.2 Member Function Documentation . . . . .	2268
15.437.2.1 desc() . . . . .	2268
15.437.2.2 operator bool() . . . . .	2269
15.437.2.3 valid() . . . . .	2269
15.438 L4virtio::Virtqueue Class Reference . . . . .	2270
15.438.1 Detailed Description . . . . .	2273
15.438.2 Member Function Documentation . . . . .	2273
15.438.2.1 avail_align() . . . . .	2273
15.438.2.2 avail_size() . . . . .	2274
15.438.2.3 desc_align() . . . . .	2275

15.438.2.4 desc_size()	2275
15.438.2.5 disable()	2276
15.438.2.6 dump()	2277
15.438.2.7 get_avail_idx()	2278
15.438.2.8 get_tail_avail_idx()	2278
15.438.2.9 no_notify_guest()	2278
15.438.2.10 no_notify_host() [1/2]	2279
15.438.2.11 no_notify_host() [2/2]	2279
15.438.2.12 num()	2280
15.438.2.13 ready()	2281
15.438.2.14 setup()	2281
15.438.2.15 setup_simple()	2283
15.438.2.16 total_size() [1/2]	2284
15.438.2.17 total_size() [2/2]	2284
15.438.2.18 used_align()	2285
15.438.2.19 used_size()	2285
15.439 L4virtio::Virtqueue::Avail Class Reference	2287
15.439.1 Detailed Description	2288
15.440 L4virtio::Virtqueue::Avail::Flags Struct Reference	2288
15.440.1 Detailed Description	2289
15.440.2 Member Typedef Documentation	2289
15.440.2.1 no_irq_bfm_t	2289
15.441 L4virtio::Virtqueue::Desc Class Reference	2289
15.441.1 Detailed Description	2291
15.442 L4virtio::Virtqueue::Desc::Flags Struct Reference	2291
15.442.1 Detailed Description	2292
15.442.2 Member Typedef Documentation	2292
15.442.2.1 indirect_bfm_t	2292
15.442.2.2 next_bfm_t	2293
15.442.2.3 write_bfm_t	2293
15.443 L4virtio::Virtqueue::Used Class Reference	2293
15.443.1 Detailed Description	2294
15.444 L4virtio::Virtqueue::Used::Flags Struct Reference	2294
15.444.1 Detailed Description	2295
15.444.2 Member Typedef Documentation	2295
15.444.2.1 no_notify_bfm_t	2295
15.445 L4virtio::Virtqueue::Used_elem Struct Reference	2296
15.445.1 Detailed Description	2296
15.445.2 Constructor & Destructor Documentation	2297
15.445.2.1 Used_elem()	2297
15.446 l4virtio_block_config_t Struct Reference	2297
15.446.1 Detailed Description	2298



15.447 <a href="#">l4virtio_block_discard_t</a> Struct Reference . . . . .	2298
15.447.1 Detailed Description . . . . .	2298
15.448 <a href="#">l4virtio_block_header_t</a> Struct Reference . . . . .	2299
15.448.1 Detailed Description . . . . .	2299
15.449 <a href="#">l4virtio_config_hdr_t</a> Struct Reference . . . . .	2300
15.449.1 Detailed Description . . . . .	2300
15.450 <a href="#">l4virtio_config_queue_t</a> Struct Reference . . . . .	2301
15.450.1 Detailed Description . . . . .	2302
15.451 <a href="#">l4virtio_input_absinfo_t</a> Struct Reference . . . . .	2302
15.451.1 Detailed Description . . . . .	2302
15.452 <a href="#">l4virtio_input_config_t</a> Struct Reference . . . . .	2303
15.452.1 Detailed Description . . . . .	2303
15.453 <a href="#">l4virtio_input_devids_t</a> Struct Reference . . . . .	2303
15.453.1 Detailed Description . . . . .	2304
15.454 <a href="#">l4virtio_input_event_t</a> Struct Reference . . . . .	2304
15.454.1 Detailed Description . . . . .	2304
15.455 <a href="#">l4virtio_net_config_t</a> Struct Reference . . . . .	2305
15.455.1 Detailed Description . . . . .	2305
15.456 <a href="#">l4virtio_net_header_t</a> Struct Reference . . . . .	2305
15.456.1 Detailed Description . . . . .	2306
15.457 <a href="#">L4virtio_port</a> Class Reference . . . . .	2306
15.457.1 Detailed Description . . . . .	2311
15.457.2 Member Function Documentation . . . . .	2311
15.457.2.1 <a href="#">drop_requests()</a> . . . . .	2311
15.458 <a href="#">Mac_addr</a> Class Reference . . . . .	2312
15.458.1 Detailed Description . . . . .	2312
15.459 <a href="#">Mac_table&lt; Size &gt;</a> Class Template Reference . . . . .	2312
15.459.1 Detailed Description . . . . .	2313
15.459.2 Member Function Documentation . . . . .	2314
15.459.2.1 <a href="#">flush()</a> . . . . .	2314
15.459.2.2 <a href="#">learn()</a> . . . . .	2314
15.459.2.3 <a href="#">lookup()</a> . . . . .	2315
15.460 <a href="#">Net_transfer</a> Class Reference . . . . .	2315
15.460.1 Detailed Description . . . . .	2317
15.460.2 Member Function Documentation . . . . .	2317
15.460.2.1 <a href="#">cur_buf()</a> . . . . .	2317
15.460.2.2 <a href="#">done()</a> . . . . .	2317
15.461 <a href="#">Rm</a> Class Reference . . . . .	2318
15.461.1 Detailed Description . . . . .	2322
15.461.2 Member Enumeration Documentation . . . . .	2322
15.461.2.1 <a href="#">Detach_flags</a> . . . . .	2322
15.461.2.2 <a href="#">Detach_result</a> . . . . .	2323

15.461.2.3 Region_flag_shifts . . . . .	2323
15.461.3 Member Function Documentation . . . . .	2323
15.461.3.1 attach() [1/2] . . . . .	2323
15.461.3.2 attach() [2/2] . . . . .	2324
15.461.3.3 detach() [1/3] . . . . .	2326
15.461.3.4 detach() [2/3] . . . . .	2326
15.461.3.5 detach() [3/3] . . . . .	2327
15.461.3.6 find() . . . . .	2328
15.461.3.7 free_area() . . . . .	2329
15.461.3.8 get_areas() . . . . .	2329
15.461.3.9 get_info() . . . . .	2330
15.461.3.10 get_regions() . . . . .	2330
15.461.3.11 reserve_area() [1/2] . . . . .	2331
15.461.3.12 reserve_area() [2/2] . . . . .	2331
15.462 Rm::Area Struct Reference . . . . .	2332
15.462.1 Detailed Description . . . . .	2333
15.463 Rm::F Struct Reference . . . . .	2333
15.463.1 Detailed Description . . . . .	2334
15.463.2 Member Enumeration Documentation . . . . .	2334
15.463.2.1 Attach_flags . . . . .	2334
15.463.2.2 Region_flags . . . . .	2334
15.464 Rm::Region Struct Reference . . . . .	2335
15.464.1 Detailed Description . . . . .	2335
15.465 Rm::Unique_region< T > Class Template Reference . . . . .	2336
15.465.1 Detailed Description . . . . .	2338
15.465.2 Constructor & Destructor Documentation . . . . .	2338
15.465.2.1 Unique_region() [1/3] . . . . .	2338
15.465.2.2 Unique_region() [2/3] . . . . .	2339
15.465.2.3 Unique_region() [3/3] . . . . .	2339
15.465.2.4 ~Unique_region() . . . . .	2339
15.465.3 Member Function Documentation . . . . .	2339
15.465.3.1 get() . . . . .	2339
15.465.3.2 is_valid() . . . . .	2340
15.465.3.3 operator=() . . . . .	2340
15.465.3.4 release() . . . . .	2340
15.465.3.5 reset() . . . . .	2341
15.466 Switch_factory Class Reference . . . . .	2341
15.466.1 Detailed Description . . . . .	2344
15.466.2 Member Function Documentation . . . . .	2345
15.466.2.1 op_create() . . . . .	2345
15.467 Virtio_net Class Reference . . . . .	2345
15.467.1 Detailed Description . . . . .	2350

15.467.2 Member Function Documentation . . . . .	2350
15.467.2.1 notify_queue() . . . . .	2350
15.468 Virtio_net_request Class Reference . . . . .	2350
15.468.1 Detailed Description . . . . .	2351
15.468.2 Member Function Documentation . . . . .	2351
15.468.2.1 drop_requests() . . . . .	2351
15.468.2.2 get_request() . . . . .	2352
15.469 Virtio_switch Class Reference . . . . .	2353
15.469.1 Detailed Description . . . . .	2354
15.469.2 Constructor & Destructor Documentation . . . . .	2355
15.469.2.1 Virtio_switch() . . . . .	2355
15.469.3 Member Function Documentation . . . . .	2355
15.469.3.1 add_monitor_port() . . . . .	2355
15.469.3.2 add_port() . . . . .	2355
15.469.3.3 check_ports() . . . . .	2356
15.469.3.4 handle_l4virtio_port_tx() . . . . .	2356
15.469.3.5 port_available() . . . . .	2357
15.470 Virtio_vlan_mangle Class Reference . . . . .	2358
15.470.1 Detailed Description . . . . .	2358
15.470.2 Constructor & Destructor Documentation . . . . .	2359
15.470.2.1 Virtio_vlan_mangle() . . . . .	2359
15.470.3 Member Function Documentation . . . . .	2359
15.470.3.1 add() . . . . .	2359
15.470.3.2 copy_pkt() . . . . .	2360
15.470.3.3 remove() . . . . .	2360
15.470.3.4 rewrite_hdr() . . . . .	2361
<b>16 File Documentation</b>	<b>2363</b>
16.1 asm_access.h . . . . .	2363
16.2 asm_access.h . . . . .	2364
16.3 asm_access.h . . . . .	2365
16.4 asm_access.h . . . . .	2366
16.5 asm_access.h . . . . .	2366
16.6 asm_access.h . . . . .	2366
16.7 asm_access.h . . . . .	2367
16.8 asm_access.h . . . . .	2368
16.9 asm_access_gen.h . . . . .	2368
16.10 hw_mmio_register_block . . . . .	2369
16.11 hw_register_block . . . . .	2370
16.12 io_regblock.h . . . . .	2373
16.13 io_regblock_port.h . . . . .	2375
16.14 poll_timeout_counter.h . . . . .	2376

16.15 device.h . . . . .	2377
16.16 uart_16550.h . . . . .	2378
16.17 uart_16550_dw.h . . . . .	2379
16.18 uart_apb.h . . . . .	2380
16.19 uart_base.h . . . . .	2380
16.20 uart_cadence.h . . . . .	2382
16.21 uart_dcc-v6.h . . . . .	2382
16.22 uart_dm.h . . . . .	2383
16.23 uart_dummy.h . . . . .	2383
16.24 uart_geni.h . . . . .	2384
16.25 uart_imx.h . . . . .	2384
16.26 uart_leon3.h . . . . .	2385
16.27 uart_linflex.h . . . . .	2386
16.28 uart_lpuart.h . . . . .	2386
16.29 uart_mvebu.h . . . . .	2387
16.30 uart_of.h . . . . .	2387
16.31 uart_omap35x.h . . . . .	2388
16.32 uart_pl011.h . . . . .	2388
16.33 uart_s3c2410.h . . . . .	2389
16.34 uart_sa1000.h . . . . .	2390
16.35 uart_sbi.h . . . . .	2391
16.36 uart_sh.h . . . . .	2391
16.37 uart_sifive.h . . . . .	2392
16.38 uart_tegra-tcu.h . . . . .	2392
16.39 tutorial.lua . . . . .	2393
16.40 cmd_control . . . . .	2395
16.41 pkg/uvmm/configs/vmm.lua File Reference . . . . .	2396
16.41.1 Function Documentation . . . . .	2396
16.41.1.1 new_sched() . . . . .	2396
16.41.1.2 set_sched() . . . . .	2397
16.41.1.3 start_io() . . . . .	2397
16.41.1.4 start_virtio_switch() . . . . .	2398
16.41.1.5 start_virtio_switch_tbl() . . . . .	2398
16.41.1.6 start_vm() . . . . .	2399
16.42 vmm.lua . . . . .	2400
16.43 debug.h . . . . .	2404
16.44 l4/re/c/debug.h File Reference . . . . .	2405
16.44.1 Detailed Description . . . . .	2406
16.45 debug.h . . . . .	2406
16.46 filter.cc . . . . .	2407
16.47 filter.h . . . . .	2407
16.48 mac_addr.h . . . . .	2408

16.49 <a href="#">mac_table.h</a>	2409
16.50 <a href="#">main.cc</a>	2410
16.51 <a href="#">Makefile</a>	2419
16.52 <a href="#">Makefile</a>	2419
16.53 <a href="#">Makefile</a>	2419
16.54 <a href="#">Makefile</a>	2419
16.55 <a href="#">options.cc</a>	2419
16.56 <a href="#">options.h</a>	2422
16.57 <a href="#">port.h</a>	2422
16.58 <a href="#">port_ixl.h</a>	2425
16.59 <a href="#">port_l4virtio.h</a>	2427
16.60 <a href="#">request.h</a>	2430
16.61 <a href="#">request_ixl.h</a>	2432
16.62 <a href="#">request_l4virtio.h</a>	2433
16.63 <a href="#">stats.h</a>	2436
16.64 <a href="#">switch.cc</a>	2437
16.65 <a href="#">switch.h</a>	2440
16.66 <a href="#">virtio_net.h</a>	2441
16.67 <a href="#">virtio_net.h</a>	2445
16.68 <a href="#">virtio_net_buffer.h</a>	2445
16.69 <a href="#">vlan.h</a>	2446
16.70 <a href="#">amd64/l4/sys/segment.h</a> File Reference	2447
16.70.1 Detailed Description	2449
16.70.2 Enumeration Type Documentation	2449
16.70.2.1 <a href="#">L4_sys_segment</a>	2449
16.70.2.2 <a href="#">L4_task_ldt_x86_consts</a>	2449
16.70.3 Function Documentation	2449
16.70.3.1 <a href="#">fiasco_amd64_segment_info()</a>	2449
16.70.3.2 <a href="#">fiasco_amd64_set_fs()</a>	2450
16.70.3.3 <a href="#">fiasco_amd64_set_segment_base()</a>	2451
16.71 <a href="#">segment.h</a>	2452
16.72 <a href="#">x86/l4/sys/segment.h</a> File Reference	2454
16.72.1 Detailed Description	2455
16.72.2 Enumeration Type Documentation	2455
16.72.2.1 <a href="#">L4_task_ldt_x86_consts</a>	2455
16.73 <a href="#">segment.h</a>	2455
16.74 <a href="#">amd64/l4/util/perform.h</a> File Reference	2456
16.74.1 Detailed Description	2457
16.75 <a href="#">perform.h</a>	2457
16.76 <a href="#">x86/l4/util/perform.h</a> File Reference	2462
16.76.1 Detailed Description	2463
16.77 <a href="#">perform.h</a>	2463

16.78 amd64/l4/util/port_io.h File Reference	2468
16.78.1 Detailed Description	2470
16.79 port_io.h	2470
16.80 x86/l4/util/port_io.h File Reference	2472
16.80.1 Detailed Description	2474
16.81 port_io.h	2474
16.82 amd64/l4/util/rdtsc.h File Reference	2476
16.82.1 Detailed Description	2478
16.83 rdtsc.h	2478
16.84 x86/l4/util/rdtsc.h File Reference	2480
16.84.1 Detailed Description	2482
16.85 rdtsc.h	2482
16.86 amd64/l4/util/spin.h File Reference	2485
16.86.1 Detailed Description	2485
16.87 spin.h	2486
16.88 x86/l4/util/spin.h File Reference	2486
16.88.1 Detailed Description	2487
16.89 spin.h	2487
16.90 __kip-arch.h	2487
16.91 __kip-arch.h	2487
16.92 __kip-arch.h	2488
16.93 __kip-arch.h	2488
16.94 amd64/l4/sys/__vcpu-arch.h File Reference	2488
16.94.1 Detailed Description	2490
16.94.2 Enumeration Type Documentation	2490
16.94.2.1 anonymous enum	2490
16.95 __vcpu-arch.h	2490
16.96 arm/l4/sys/__vcpu-arch.h File Reference	2491
16.96.1 Detailed Description	2492
16.96.2 Enumeration Type Documentation	2492
16.96.2.1 anonymous enum	2492
16.96.2.2 L4_vcpu_e_field_ids	2493
16.97 __vcpu-arch.h	2493
16.98 arm64/l4/sys/__vcpu-arch.h File Reference	2494
16.98.1 Detailed Description	2495
16.98.2 Enumeration Type Documentation	2496
16.98.2.1 anonymous enum	2496
16.98.2.2 L4_vcpu_e_field_ids	2496
16.99 __vcpu-arch.h	2496
16.100 x86/l4/sys/__vcpu-arch.h File Reference	2497
16.100.1 Detailed Description	2499
16.100.2 Enumeration Type Documentation	2499

16.100.2.1 anonymous enum . . . . .	2499
16.101 __vcpu-arch.h . . . . .	2499
16.102 ktrace_events.h . . . . .	2500
16.103 ktrace_events.h . . . . .	2503
16.104 ktrace_events.h . . . . .	2506
16.105 ktrace_events.h . . . . .	2509
16.106 amd64/l4/sys/linkage.h File Reference . . . . .	2512
16.106.1 Detailed Description . . . . .	2513
16.107 linkage.h . . . . .	2513
16.108 arm/l4/sys/linkage.h File Reference . . . . .	2513
16.108.1 Detailed Description . . . . .	2513
16.109 linkage.h . . . . .	2514
16.110 linkage.h . . . . .	2514
16.111 x86/l4/sys/linkage.h File Reference . . . . .	2514
16.111.1 Detailed Description . . . . .	2514
16.112 linkage.h . . . . .	2515
16.113 arm/l4/sys/mem_op.h File Reference . . . . .	2515
16.113.1 Detailed Description . . . . .	2516
16.114 mem_op.h . . . . .	2516
16.115 arm/l4/sys/syscall_defs.h File Reference . . . . .	2517
16.115.1 Detailed Description . . . . .	2518
16.116 syscall_defs.h . . . . .	2518
16.117 vm.h . . . . .	2518
16.118 arm/l4/sys/vm.h File Reference . . . . .	2518
16.118.1 Detailed Description . . . . .	2519
16.119 vm.h . . . . .	2519
16.120 vm.h . . . . .	2520
16.121 vm.h . . . . .	2520
16.122 amd64/l4/util/arch/l4_macros.h File Reference . . . . .	2521
16.122.1 Detailed Description . . . . .	2521
16.123 l4_macros.h . . . . .	2521
16.124 arm/l4/util/arch/l4_macros.h File Reference . . . . .	2521
16.124.1 Detailed Description . . . . .	2521
16.125 l4_macros.h . . . . .	2522
16.126 l4/util/l4_macros.h File Reference . . . . .	2522
16.126.1 Detailed Description . . . . .	2522
16.127 l4_macros.h . . . . .	2523
16.128 x86/l4/util/arch/l4_macros.h File Reference . . . . .	2523
16.128.1 Detailed Description . . . . .	2523
16.129 l4_macros.h . . . . .	2523
16.130 thread.h . . . . .	2524
16.131 thread.h . . . . .	2524

16.132 arm/l4/sys/arch/thread.h File Reference . . . . .	2524
16.132.1 Detailed Description . . . . .	2524
16.133 thread.h . . . . .	2525
16.134 thread.h . . . . .	2525
16.135 arm64/l4/sys/arch/thread.h File Reference . . . . .	2525
16.135.1 Detailed Description . . . . .	2526
16.136 thread.h . . . . .	2526
16.137 l4/sys/thread.h File Reference . . . . .	2526
16.137.1 Detailed Description . . . . .	2529
16.138 thread.h . . . . .	2529
16.139 l4/util/thread.h File Reference . . . . .	2536
16.139.1 Detailed Description . . . . .	2537
16.139.2 Macro Definition Documentation . . . . .	2537
16.139.2.1 __L4UTIL_THREAD_FUNC . . . . .	2537
16.140 thread.h . . . . .	2538
16.141 thread.h . . . . .	2538
16.142 thread.h . . . . .	2538
16.143 amd64/l4/util/bitops_arch.h File Reference . . . . .	2538
16.143.1 Detailed Description . . . . .	2539
16.144 bitops_arch.h . . . . .	2539
16.145 arm/l4/util/bitops_arch.h File Reference . . . . .	2542
16.145.1 Detailed Description . . . . .	2542
16.146 bitops_arch.h . . . . .	2543
16.147 x86/l4/util/bitops_arch.h File Reference . . . . .	2543
16.147.1 Detailed Description . . . . .	2543
16.148 bitops_arch.h . . . . .	2543
16.149 amd64/l4/util/cpu.h File Reference . . . . .	2546
16.149.1 Detailed Description . . . . .	2547
16.150 cpu.h . . . . .	2547
16.151 arm/l4/util/cpu.h File Reference . . . . .	2548
16.151.1 Detailed Description . . . . .	2548
16.152 cpu.h . . . . .	2548
16.153 x86/l4/util/cpu.h File Reference . . . . .	2549
16.153.1 Detailed Description . . . . .	2549
16.154 cpu.h . . . . .	2550
16.155 amd64/l4/util/mbi_argv.h File Reference . . . . .	2551
16.155.1 Detailed Description . . . . .	2551
16.156 mbi_argv.h . . . . .	2552
16.157 arm/l4/util/mbi_argv.h File Reference . . . . .	2552
16.157.1 Detailed Description . . . . .	2553
16.158 mbi_argv.h . . . . .	2553
16.159 x86/l4/util/mbi_argv.h File Reference . . . . .	2553



16.159.1 Detailed Description . . . . .	2554
16.160 mbi_argv.h . . . . .	2554
16.161 contrib/libio-io/l4/io/io.h File Reference . . . . .	2555
16.161.1 Function Documentation . . . . .	2556
16.161.1.1 l4io_get_root_device() . . . . .	2556
16.161.1.2 l4io_iterate_devices() . . . . .	2556
16.161.1.3 l4io_request_all_ioports() . . . . .	2557
16.161.1.4 l4io_request_icu() . . . . .	2557
16.162 io.h . . . . .	2557
16.163 l4/cxx/alloc.h File Reference . . . . .	2558
16.163.1 Detailed Description . . . . .	2559
16.164 alloc.h . . . . .	2559
16.165 arith . . . . .	2559
16.166 l4/cxx/avl_map File Reference . . . . .	2560
16.166.1 Detailed Description . . . . .	2562
16.167 avl_map . . . . .	2562
16.168 l4/cxx/avl_set File Reference . . . . .	2563
16.168.1 Detailed Description . . . . .	2564
16.169 avl_set . . . . .	2565
16.170 l4/cxx/avl_tree File Reference . . . . .	2568
16.170.1 Detailed Description . . . . .	2570
16.171 avl_tree . . . . .	2570
16.172 l4/cxx/basic_ostream File Reference . . . . .	2574
16.172.1 Detailed Description . . . . .	2575
16.173 basic_ostream . . . . .	2575
16.174 l4/cxx/basic_vector.h File Reference . . . . .	2578
16.174.1 Detailed Description . . . . .	2578
16.175 basic_vector.h . . . . .	2579
16.176 bitfield . . . . .	2579
16.177 bitmap . . . . .	2581
16.178 l4/cxx/bits/bst.h File Reference . . . . .	2584
16.178.1 Detailed Description . . . . .	2586
16.179 bst.h . . . . .	2586
16.180 l4/cxx/bits/bst_base.h File Reference . . . . .	2588
16.180.1 Detailed Description . . . . .	2590
16.181 bst_base.h . . . . .	2590
16.182 l4/cxx/bits/bst_iter.h File Reference . . . . .	2591
16.182.1 Detailed Description . . . . .	2592
16.183 bst_iter.h . . . . .	2593
16.184 list_basics.h . . . . .	2594
16.185 l4/cxx/bits/smart_ptr_list.h File Reference . . . . .	2596
16.185.1 Detailed Description . . . . .	2597

16.186 smart_ptr_list.h	2597
16.187 type_traits.h	2599
16.188 dlist	2602
16.189 elide_dtor	2607
16.190 l4/cxx/exceptions File Reference	2608
16.190.1 Detailed Description	2609
16.191 exceptions	2609
16.192 hlist	2612
16.193 l4/cxx/iostream File Reference	2614
16.193.1 Detailed Description	2614
16.194 iostream	2614
16.195 l4/cxx/ipc_helper File Reference	2615
16.195.1 Detailed Description	2616
16.196 ipc_helper	2616
16.197 l4/cxx/ipc_stream File Reference	2616
16.197.1 Detailed Description	2619
16.197.2 Function Documentation	2619
16.197.2.1 operator<<() [1/4]	2619
16.197.2.2 operator<<() [2/4]	2620
16.197.2.3 operator<<() [3/4]	2620
16.197.2.4 operator<<() [4/4]	2621
16.197.2.5 operator>>() [1/6]	2622
16.197.2.6 operator>>() [2/6]	2622
16.197.2.7 operator>>() [3/6]	2623
16.197.2.8 operator>>() [4/6]	2624
16.197.2.9 operator>>() [5/6]	2625
16.197.2.10 operator>>() [6/6]	2625
16.198 ipc_stream	2626
16.199 ipc_timeout_queue	2634
16.200 l4/cxx/l4iostream File Reference	2636
16.200.1 Detailed Description	2636
16.201 l4iostream	2637
16.202 l4/cxx/l4types.h File Reference	2637
16.202.1 Detailed Description	2638
16.203 l4types.h	2638
16.204 list	2638
16.205 list_alloc	2642
16.206 l4/cxx/lock_guard.h File Reference	2648
16.206.1 Detailed Description	2648
16.207 lock_guard.h	2648
16.208 l4/cxx/main_thread File Reference	2649
16.208.1 Detailed Description	2650

16.209 main_thread . . . . .	2650
16.210 minmax . . . . .	2651
16.211 numeric . . . . .	2652
16.212 observer . . . . .	2652
16.213 l4/cxx/pair File Reference . . . . .	2653
16.213.1 Detailed Description . . . . .	2654
16.214 pair . . . . .	2654
16.215 ref_ptr . . . . .	2655
16.216 l4/cxx/ref_ptr_list File Reference . . . . .	2658
16.216.1 Detailed Description . . . . .	2659
16.217 ref_ptr_list . . . . .	2659
16.218 slab_alloc . . . . .	2660
16.219 slist . . . . .	2663
16.220 static_container . . . . .	2666
16.221 static_vector . . . . .	2666
16.222 std_alloc . . . . .	2667
16.223 std_ops . . . . .	2668
16.224 string . . . . .	2668
16.225 l4/cxx/string.h File Reference . . . . .	2671
16.225.1 Detailed Description . . . . .	2672
16.226 string.h . . . . .	2672
16.227 type_list . . . . .	2673
16.228 type_traits . . . . .	2673
16.229 unique_ptr . . . . .	2678
16.230 l4/cxx/unique_ptr_list File Reference . . . . .	2679
16.230.1 Detailed Description . . . . .	2680
16.231 unique_ptr_list . . . . .	2681
16.232 utils . . . . .	2681
16.233 weak_ref . . . . .	2681
16.234 amd64/l4/util/irq.h File Reference . . . . .	2683
16.234.1 Detailed Description . . . . .	2683
16.235 irq.h . . . . .	2684
16.236 arm/l4/util/irq.h File Reference . . . . .	2684
16.236.1 Detailed Description . . . . .	2685
16.237 irq.h . . . . .	2685
16.238 l4/irq/irq.h File Reference . . . . .	2686
16.238.1 Detailed Description . . . . .	2687
16.239 irq.h . . . . .	2687
16.240 l4/sys/irq.h File Reference . . . . .	2688
16.240.1 Detailed Description . . . . .	2690
16.241 irq.h . . . . .	2690
16.242 x86/l4/util/irq.h File Reference . . . . .	2692

16.242.1 Detailed Description . . . . .	2693
16.243 irq.h . . . . .	2693
16.244 backend . . . . .	2694
16.245 default_ops_impl.h . . . . .	2697
16.246 fd_store.h . . . . .	2698
16.247 fd_store_impl.h . . . . .	2699
16.248 ns_fs.h . . . . .	2699
16.249 ns_fs_impl.h . . . . .	2700
16.250 ro_file.h . . . . .	2705
16.251 ro_file_impl.h . . . . .	2705
16.252 vcon_stream.h . . . . .	2707
16.253 vcon_stream_impl.h . . . . .	2707
16.254 vfs_impl.h . . . . .	2710
16.255 vfs.h . . . . .	2722
16.256 virtio-net . . . . .	2731
16.257 l4virtio . . . . .	2734
16.258 l4virtio . . . . .	2736
16.259 l4virtio . . . . .	2738
16.260 virtio . . . . .	2749
16.261 virtio-block . . . . .	2753
16.262 virtio-block . . . . .	2757
16.263 virtio-console . . . . .	2763
16.264 virtio-console-device . . . . .	2769
16.265 virtio-gpio-device . . . . .	2773
16.266 virtio-i2c-device . . . . .	2778
16.267 virtio-rng-device . . . . .	2783
16.268 virtio-scmi-device . . . . .	2785
16.269 virtio-spi-device . . . . .	2794
16.270 virtio.h . . . . .	2799
16.271 virtio_block.h . . . . .	2802
16.272 virtio_input.h . . . . .	2803
16.273 virtqueue . . . . .	2803
16.274 l4/libedid/edid.h File Reference . . . . .	2808
16.275 edid.h . . . . .	2809
16.276 l4/re/c/dataspace.h File Reference . . . . .	2809
16.276.1 Detailed Description . . . . .	2811
16.277 dataspace.h . . . . .	2811
16.278 l4/re/c/dma_space.h File Reference . . . . .	2812
16.278.1 Detailed Description . . . . .	2813
16.278.2 Enumeration Type Documentation . . . . .	2813
16.278.2.1 l4re_dma_space_direction . . . . .	2813
16.278.2.2 l4re_dma_space_space_attrs . . . . .	2814

16.279 dma_space.h . . . . .	2814
16.280 l4/re/c/event.h File Reference . . . . .	2815
16.280.1 Detailed Description . . . . .	2816
16.281 event.h . . . . .	2816
16.282 l4/re/event.h File Reference . . . . .	2817
16.282.1 Detailed Description . . . . .	2818
16.283 event.h . . . . .	2818
16.284 event_buffer.h . . . . .	2819
16.285 l4/re/c/inhibitor.h File Reference . . . . .	2819
16.285.1 Detailed Description . . . . .	2820
16.285.2 Function Documentation . . . . .	2820
16.285.2.1 l4re_inhibitor_acquire() . . . . .	2820
16.285.2.2 l4re_inhibitor_next_lock_info() . . . . .	2821
16.285.2.3 l4re_inhibitor_release() . . . . .	2822
16.286 inhibitor.h . . . . .	2822
16.287 l4/re/c/log.h File Reference . . . . .	2823
16.287.1 Detailed Description . . . . .	2823
16.288 log.h . . . . .	2823
16.289 l4/re/c/mem_alloc.h File Reference . . . . .	2824
16.289.1 Detailed Description . . . . .	2825
16.290 mem_alloc.h . . . . .	2825
16.291 l4/re/c/namespace.h File Reference . . . . .	2826
16.291.1 Detailed Description . . . . .	2827
16.292 namespace.h . . . . .	2827
16.293 l4/re/c/parent.h File Reference . . . . .	2827
16.293.1 Detailed Description . . . . .	2828
16.293.2 Function Documentation . . . . .	2828
16.293.2.1 l4re_parent_signal() . . . . .	2828
16.294 parent.h . . . . .	2829
16.295 l4/re/c/rm.h File Reference . . . . .	2829
16.295.1 Detailed Description . . . . .	2831
16.296 rm.h . . . . .	2831
16.297 l4/re/c/util/cap_alloc.h File Reference . . . . .	2833
16.297.1 Detailed Description . . . . .	2834
16.298 cap_alloc.h . . . . .	2834
16.299 l4/re/c/util/kumem_alloc.h File Reference . . . . .	2835
16.299.1 Detailed Description . . . . .	2835
16.299.2 Function Documentation . . . . .	2836
16.299.2.1 l4re_util_kumem_alloc() . . . . .	2836
16.300 kumem_alloc.h . . . . .	2836
16.301 l4/re/c/util/video/goos_fb.h File Reference . . . . .	2837
16.301.1 Detailed Description . . . . .	2837

16.302	goos_fb.h	2837
16.303	l4/re/c/video/colors.h File Reference	2838
16.303.1	Detailed Description	2839
16.304	colors.h	2840
16.305	l4/re/c/video/goos.h File Reference	2840
16.305.1	Detailed Description	2842
16.306	goos.h	2842
16.307	l4/re/c/video/view.h File Reference	2843
16.307.1	Detailed Description	2844
16.308	view.h	2845
16.309	console	2846
16.310	l4/re/dataspace File Reference	2846
16.310.1	Detailed Description	2847
16.311	dataspace	2847
16.312	l4/re/dataspace-sys.h File Reference	2849
16.312.1	Detailed Description	2849
16.313	dataspace-sys.h	2850
16.314	dbg_events	2850
16.315	l4/re/dma_space File Reference	2850
16.316	dma_space	2852
16.317	l4/re/elf_aux.h File Reference	2853
16.317.1	Detailed Description	2854
16.318	elf_aux.h	2854
16.319	l4/re/env File Reference	2855
16.319.1	Detailed Description	2856
16.320	env	2856
16.321	l4/re/env.h File Reference	2857
16.321.1	Detailed Description	2859
16.321.2	Typedef Documentation	2859
16.321.2.1	l4re_env_t	2859
16.322	env.h	2859
16.323	l4/re/error_helper File Reference	2861
16.323.1	Detailed Description	2862
16.324	error_helper	2862
16.325	event-sys.h	2864
16.326	event_enums.h	2864
16.327	l4/re/impl/dataspace_impl.h File Reference	2870
16.327.1	Detailed Description	2871
16.328	dataspace_impl.h	2871
16.329	l4/re/impl/mem_alloc_impl.h File Reference	2873
16.329.1	Detailed Description	2873
16.330	mem_alloc_impl.h	2874

16.331 l4/re/impl/namespace_impl.h File Reference . . . . .	2874
16.331.1 Detailed Description . . . . .	2875
16.332 namespace_impl.h . . . . .	2875
16.333 l4/re/impl/rm_impl.h File Reference . . . . .	2877
16.333.1 Detailed Description . . . . .	2877
16.334 rm_impl.h . . . . .	2878
16.335 inhibitor . . . . .	2879
16.336 inhibitor-sys.h . . . . .	2879
16.337 itas . . . . .	2880
16.338 l4/re/l4aux.h File Reference . . . . .	2881
16.338.1 Detailed Description . . . . .	2881
16.339 l4aux.h . . . . .	2882
16.340 l4/re/log File Reference . . . . .	2882
16.340.1 Detailed Description . . . . .	2883
16.341 log . . . . .	2883
16.342 l4/re/log-sys.h File Reference . . . . .	2884
16.342.1 Detailed Description . . . . .	2884
16.343 log-sys.h . . . . .	2884
16.344 l4/re/mem_alloc File Reference . . . . .	2884
16.344.1 Detailed Description . . . . .	2886
16.345 mem_alloc . . . . .	2886
16.346 l4/re/mem_alloc-sys.h File Reference . . . . .	2887
16.346.1 Detailed Description . . . . .	2887
16.347 mem_alloc-sys.h . . . . .	2887
16.348 l4/re/mmio_space File Reference . . . . .	2888
16.348.1 Detailed Description . . . . .	2888
16.349 mmio_space . . . . .	2889
16.350 l4/re/namespace File Reference . . . . .	2889
16.350.1 Detailed Description . . . . .	2891
16.351 namespace . . . . .	2891
16.352 l4/re/namespace-sys.h File Reference . . . . .	2892
16.352.1 Detailed Description . . . . .	2892
16.353 namespace-sys.h . . . . .	2893
16.354 l4/re/parent File Reference . . . . .	2893
16.354.1 Detailed Description . . . . .	2894
16.355 parent . . . . .	2894
16.356 l4/re/parent-sys.h File Reference . . . . .	2895
16.356.1 Detailed Description . . . . .	2895
16.357 parent-sys.h . . . . .	2895
16.358 l4/re/protocols.h File Reference . . . . .	2895
16.358.1 Detailed Description . . . . .	2896
16.359 protocols.h . . . . .	2896

16.360 l4/re/random File Reference . . . . .	2896
16.360.1 Detailed Description . . . . .	2897
16.361 random . . . . .	2898
16.362 remote_access . . . . .	2898
16.363 l4/re/rm File Reference . . . . .	2899
16.363.1 Detailed Description . . . . .	2900
16.364 rm . . . . .	2900
16.365 l4/re/rm-sys.h File Reference . . . . .	2904
16.365.1 Detailed Description . . . . .	2904
16.366 rm-sys.h . . . . .	2905
16.367 l4/re/util/bitmap_cap_alloc File Reference . . . . .	2905
16.367.1 Detailed Description . . . . .	2906
16.368 bitmap_cap_alloc . . . . .	2906
16.369 br_manager . . . . .	2907
16.370 l4/re/util/cap File Reference . . . . .	2909
16.370.1 Detailed Description . . . . .	2910
16.371 cap . . . . .	2910
16.372 l4/re/cap_alloc File Reference . . . . .	2911
16.372.1 Detailed Description . . . . .	2912
16.373 cap_alloc . . . . .	2912
16.374 l4/re/util/cap_alloc File Reference . . . . .	2914
16.374.1 Detailed Description . . . . .	2916
16.375 cap_alloc . . . . .	2916
16.376 l4/re/util/cap_alloc_impl.h File Reference . . . . .	2917
16.376.1 Detailed Description . . . . .	2918
16.377 cap_alloc_impl.h . . . . .	2918
16.378 l4/re/util/counting_cap_alloc File Reference . . . . .	2919
16.378.1 Detailed Description . . . . .	2921
16.379 counting_cap_alloc . . . . .	2921
16.380 dataspace_svr . . . . .	2924
16.381 l4/re/debug File Reference . . . . .	2927
16.381.1 Detailed Description . . . . .	2928
16.382 debug . . . . .	2929
16.383 debug . . . . .	2929
16.384 env_ns . . . . .	2931
16.385 event . . . . .	2932
16.386 l4/re/util/event File Reference . . . . .	2934
16.387 event . . . . .	2935
16.388 event_buffer . . . . .	2937
16.389 event_svr . . . . .	2938
16.390 icu_svr . . . . .	2939
16.391 l4/re/util/item_alloc File Reference . . . . .	2941



16.391.1 Detailed Description . . . . .	2943
16.392 item_alloc . . . . .	2943
16.393 l4/re/util/kumem_alloc File Reference . . . . .	2944
16.393.1 Detailed Description . . . . .	2945
16.394 kumem_alloc . . . . .	2945
16.395 name_space_svr . . . . .	2945
16.396 object_registry . . . . .	2951
16.397 poll_timeout_kipclock . . . . .	2953
16.398 l4/re/util/region_mapping File Reference . . . . .	2954
16.398.1 Detailed Description . . . . .	2955
16.399 region_mapping . . . . .	2955
16.400 region_mapping_svr . . . . .	2961
16.401 l4/re/shared_cap File Reference . . . . .	2964
16.401.1 Detailed Description . . . . .	2966
16.402 shared_cap . . . . .	2966
16.403 l4/re/util/shared_cap File Reference . . . . .	2966
16.403.1 Detailed Description . . . . .	2968
16.404 shared_cap . . . . .	2968
16.405 l4/re/unique_cap File Reference . . . . .	2969
16.405.1 Detailed Description . . . . .	2970
16.406 unique_cap . . . . .	2970
16.407 l4/re/util/unique_cap File Reference . . . . .	2971
16.407.1 Detailed Description . . . . .	2972
16.408 unique_cap . . . . .	2972
16.409 vcon_svr . . . . .	2973
16.410 goos_fb . . . . .	2974
16.411 goos_svr . . . . .	2976
16.412 colors . . . . .	2977
16.413 goos . . . . .	2979
16.414 l4/re/video/goos-sys.h File Reference . . . . .	2982
16.414.1 Detailed Description . . . . .	2982
16.415 goos-sys.h . . . . .	2983
16.416 view . . . . .	2983
16.417 l4/shmc/ringbuf.h File Reference . . . . .	2983
16.417.1 Function Documentation . . . . .	2985
16.417.1.1 l4shmc_rb_attach_receiver() . . . . .	2985
16.417.1.2 l4shmc_rb_attach_sender() . . . . .	2985
16.417.1.3 l4shmc_rb_deinit_buffer() . . . . .	2986
16.417.1.4 l4shmc_rb_init_buffer() . . . . .	2986
16.417.1.5 l4shmc_rb_init_receiver() . . . . .	2987
16.417.1.6 l4shmc_rb_receiver_copy_out() . . . . .	2987
16.417.1.7 l4shmc_rb_receiver_notify_done() . . . . .	2988

16.417.1.8 l4shmc_rb_receiver_read_next_size()	2988
16.417.1.9 l4shmc_rb_receiver_wait_for_data()	2988
16.417.1.10 l4shmc_rb_sender_alloc_packet()	2989
16.417.1.11 l4shmc_rb_sender_commit_packet()	2989
16.417.1.12 l4shmc_rb_sender_next_copy_in()	2989
16.417.1.13 l4shmc_rb_sender_put_data()	2990
16.418 ringbuf.h	2990
16.419 l4/shmc/shmc.h File Reference	2992
16.419.1 Detailed Description	2995
16.420 shmc.h	2995
16.421 l4/sigma0/sigma0.h File Reference	2997
16.421.1 Detailed Description	2999
16.422 sigma0.h	2999
16.423 __kernel_object_impl.h	3001
16.424 l4/sys/__ktrace-impl.h File Reference	3001
16.424.1 Detailed Description	3002
16.425 __ktrace-impl.h	3002
16.426 __l4_fpage.h	3003
16.427 __platform_control-arm.h	3007
16.428 __task-arm.h	3008
16.429 __timeout.h	3008
16.430 l4/sys/__typeinfo.h File Reference	3011
16.430.1 Detailed Description	3013
16.431 __typeinfo.h	3013
16.432 __vcpu-arm.h	3023
16.433 __vm-svm.h	3024
16.434 __vm-vmx.h	3026
16.435 l4/sys/arm_smccc File Reference	3032
16.435.1 Detailed Description	3033
16.436 arm_smccc	3033
16.437 l4/sys/arm_smccc.h File Reference	3033
16.437.1 Detailed Description	3034
16.437.2 Function Documentation	3034
16.437.2.1 l4_arm_smccc_call()	3034
16.438 arm_smccc.h	3036
16.439 amd64/l4/sys/arch/cache.h File Reference	3037
16.439.1 Detailed Description	3037
16.440 cache.h	3037
16.441 arm/l4/sys/arch/cache.h File Reference	3038
16.441.1 Detailed Description	3039
16.442 cache.h	3039
16.443 arm64/l4/sys/arch/cache.h File Reference	3040

16.443.1 Detailed Description . . . . .	3041
16.444 cache.h . . . . .	3042
16.445 l4/sys/cache.h File Reference . . . . .	3043
16.445.1 Detailed Description . . . . .	3044
16.446 cache.h . . . . .	3044
16.447 x86/l4/sys/arch/cache.h File Reference . . . . .	3044
16.447.1 Detailed Description . . . . .	3045
16.448 cache.h . . . . .	3045
16.449 l4/sys/capability File Reference . . . . .	3046
16.449.1 Detailed Description . . . . .	3047
16.449.2 Macro Definition Documentation . . . . .	3047
16.449.2.1 L4_DISABLE_COPY . . . . .	3047
16.450 capability . . . . .	3048
16.451 l4/sys/compiler.h File Reference . . . . .	3049
16.451.1 Detailed Description . . . . .	3050
16.452 compiler.h . . . . .	3051
16.453 amd64/l4/sys/arch/consts.h File Reference . . . . .	3053
16.453.1 Detailed Description . . . . .	3053
16.454 consts.h . . . . .	3054
16.455 arm/l4/sys/arch/consts.h File Reference . . . . .	3054
16.455.1 Detailed Description . . . . .	3055
16.456 consts.h . . . . .	3055
16.457 arm64/l4/sys/arch/consts.h File Reference . . . . .	3055
16.457.1 Detailed Description . . . . .	3056
16.458 consts.h . . . . .	3056
16.459 l4/re/consts.h File Reference . . . . .	3056
16.459.1 Detailed Description . . . . .	3057
16.459.2 Enumeration Type Documentation . . . . .	3058
16.459.2.1 anonymous enum . . . . .	3058
16.460 consts.h . . . . .	3058
16.461 l4/sys/consts.h File Reference . . . . .	3058
16.461.1 Detailed Description . . . . .	3060
16.461.2 Macro Definition Documentation . . . . .	3060
16.461.2.1 L4_CAP_SIZE . . . . .	3060
16.461.2.2 L4_SYSF_CALL . . . . .	3061
16.461.2.3 L4_SYSF_OPEN_WAIT . . . . .	3061
16.461.2.4 L4_SYSF_RECV . . . . .	3061
16.461.2.5 L4_SYSF_REPLY . . . . .	3061
16.461.2.6 L4_SYSF_REPLY_AND_WAIT . . . . .	3062
16.461.2.7 L4_SYSF_SEND . . . . .	3062
16.461.2.8 L4_SYSF_SEND_AND_WAIT . . . . .	3062
16.461.2.9 L4_SYSF_WAIT . . . . .	3062

16.462	consts.h	3063
16.463	x86/I4/sys/arch/consts.h File Reference	3064
16.463.1	Detailed Description	3065
16.464	consts.h	3065
16.465	capability.h	3065
16.466	I4/re/consts File Reference	3068
16.466.1	Detailed Description	3068
16.467	consts	3069
16.468	consts	3069
16.469	ipc_array	3070
16.470	ipc_basics	3073
16.471	I4/sys/cxx/ipc_client File Reference	3077
16.471.1	Macro Definition Documentation	3078
16.471.1.1	L4_RPC_DEF	3078
16.472	ipc_client	3079
16.473	ipc_epiface	3079
16.474	I4/sys/cxx/ipc_iface File Reference	3083
16.474.1	Detailed Description	3085
16.474.2	Macro Definition Documentation	3086
16.474.2.1	L4_INLINE_RPC	3086
16.474.2.2	L4_INLINE_RPC_NF	3086
16.474.2.3	L4_INLINE_RPC_NF_OP	3087
16.474.2.4	L4_INLINE_RPC_OP	3087
16.474.2.5	L4_RPC	3088
16.474.2.6	L4_RPC_NF	3088
16.474.2.7	L4_RPC_NF_OP	3089
16.474.2.8	L4_RPC_OP	3089
16.475	ipc_iface	3090
16.476	ipc_legacy	3095
16.477	ipc_ret_array	3095
16.478	I4/cxx/ipc_server File Reference	3096
16.478.1	Detailed Description	3097
16.479	ipc_server	3098
16.480	ipc_server	3098
16.481	ipc_server_loop	3103
16.482	ipc_string	3106
16.483	I4/sys/cxx/ipc_types File Reference	3107
16.484	ipc_types	3109
16.485	ipc_varg	3116
16.486	limits	3121
16.487	I4/sys/cxx/smart_capability_1x File Reference	3123
16.488	smart_capability_1x	3124

16.489 I4/sys/cxx/types File Reference . . . . .	3126
16.490 types . . . . .	3128
16.491 I4/sys/debugger File Reference . . . . .	3132
16.491.1 Detailed Description . . . . .	3132
16.492 debugger . . . . .	3133
16.493 I4/sys/debugger.h File Reference . . . . .	3133
16.493.1 Detailed Description . . . . .	3135
16.493.2 Enumeration Type Documentation . . . . .	3135
16.493.2.1 anonymous enum . . . . .	3135
16.494 debugger.h . . . . .	3136
16.495 I4/sys/err.h File Reference . . . . .	3139
16.495.1 Detailed Description . . . . .	3140
16.496 err.h . . . . .	3141
16.497 I4/sys/exception File Reference . . . . .	3141
16.497.1 Detailed Description . . . . .	3142
16.498 exception . . . . .	3143
16.499 I4/sys/factory File Reference . . . . .	3143
16.499.1 Detailed Description . . . . .	3144
16.500 factory . . . . .	3144
16.501 I4/sys/factory.h File Reference . . . . .	3146
16.501.1 Detailed Description . . . . .	3148
16.502 factory.h . . . . .	3148
16.503 I4/sys/icu File Reference . . . . .	3153
16.503.1 Detailed Description . . . . .	3154
16.504 icu . . . . .	3154
16.505 I4/sys/icu.h File Reference . . . . .	3154
16.505.1 Detailed Description . . . . .	3156
16.506 icu.h . . . . .	3157
16.507 iommu . . . . .	3160
16.508 ipc.h . . . . .	3160
16.509 ipc.h . . . . .	3161
16.510 ipc.h . . . . .	3161
16.511 I4/sys/ipc.h File Reference . . . . .	3162
16.511.1 Detailed Description . . . . .	3164
16.511.2 Function Documentation . . . . .	3165
16.511.2.1 I4_ipc_to_errno() . . . . .	3165
16.512 ipc.h . . . . .	3165
16.513 x86/I4/sys/arch/ipc.h File Reference . . . . .	3168
16.513.1 Detailed Description . . . . .	3169
16.514 ipc.h . . . . .	3169
16.515 I4/sys/ipc_gate File Reference . . . . .	3170
16.515.1 Detailed Description . . . . .	3171

16.516 ipc_gate . . . . .	3172
16.517 l4/sys/ipc_gate.h File Reference . . . . .	3172
16.517.1 Detailed Description . . . . .	3173
16.518 ipc_gate.h . . . . .	3174
16.519 l4/sys/irq File Reference . . . . .	3175
16.519.1 Detailed Description . . . . .	3177
16.520 irq . . . . .	3177
16.521 l4/sys/kdebug.h File Reference . . . . .	3179
16.521.1 Detailed Description . . . . .	3180
16.521.2 Enumeration Type Documentation . . . . .	3181
16.521.2.1 l4_kdebug_ops_t . . . . .	3181
16.521.3 Function Documentation . . . . .	3181
16.521.3.1 __l4_kdebug_3_text() . . . . .	3181
16.521.3.2 __l4_kdebug_op() . . . . .	3182
16.521.3.3 __l4_kdebug_op_1() . . . . .	3183
16.521.3.4 __l4_kdebug_text() . . . . .	3185
16.521.3.5 l4_kd_enter() . . . . .	3187
16.521.3.6 l4_kd_outchar() . . . . .	3187
16.521.3.7 l4_kd_outdec() . . . . .	3188
16.521.3.8 l4_kd_outhex12() . . . . .	3189
16.521.3.9 l4_kd_outhex16() . . . . .	3189
16.521.3.10 l4_kd_outhex20() . . . . .	3190
16.521.3.11 l4_kd_outhex32() . . . . .	3190
16.521.3.12 l4_kd_outhex64() . . . . .	3191
16.521.3.13 l4_kd_outhex8() . . . . .	3191
16.521.3.14 l4_kd_outnstring() . . . . .	3192
16.521.3.15 l4_kd_outstring() . . . . .	3193
16.521.3.16 l4_kd_outumword() . . . . .	3193
16.522 kdebug.h . . . . .	3194
16.523 l4/sys/kdump.h File Reference . . . . .	3196
16.523.1 Detailed Description . . . . .	3197
16.523.2 Function Documentation . . . . .	3197
16.523.2.1 fiasco_dump_kmem_stats() . . . . .	3197
16.524 kdump.h . . . . .	3198
16.525 l4/sys/kernel_object.h File Reference . . . . .	3198
16.525.1 Detailed Description . . . . .	3199
16.526 kernel_object.h . . . . .	3199
16.527 l4/sys/kip File Reference . . . . .	3200
16.527.1 Detailed Description . . . . .	3201
16.528 kip . . . . .	3201
16.529 kobject . . . . .	3203
16.530 l4/sys/ktrace.h File Reference . . . . .	3203

16.530.1 Detailed Description . . . . .	3204
16.531 ktrace.h . . . . .	3205
16.532 amd64/l4/sys/arch/l4int.h File Reference . . . . .	3205
16.532.1 Detailed Description . . . . .	3205
16.533 l4int.h . . . . .	3206
16.534 arm/l4/sys/arch/l4int.h File Reference . . . . .	3206
16.534.1 Detailed Description . . . . .	3206
16.535 l4int.h . . . . .	3206
16.536 arm64/l4/sys/arch/l4int.h File Reference . . . . .	3207
16.536.1 Detailed Description . . . . .	3207
16.537 l4int.h . . . . .	3207
16.538 l4/sys/l4int.h File Reference . . . . .	3208
16.538.1 Detailed Description . . . . .	3209
16.539 l4int.h . . . . .	3209
16.540 x86/l4/sys/arch/l4int.h File Reference . . . . .	3209
16.540.1 Detailed Description . . . . .	3210
16.541 l4int.h . . . . .	3210
16.542 l4/sys/memdesc.h File Reference . . . . .	3210
16.542.1 Detailed Description . . . . .	3211
16.543 memdesc.h . . . . .	3212
16.544 meta . . . . .	3213
16.545 l4/sys/meta File Reference . . . . .	3214
16.545.1 Detailed Description . . . . .	3215
16.546 meta . . . . .	3215
16.547 l4/sys/obj_info.h File Reference . . . . .	3215
16.547.1 Detailed Description . . . . .	3216
16.547.2 Function Documentation . . . . .	3217
16.547.2.1 l4_debugger_query_obj_infos() . . . . .	3217
16.548 obj_info.h . . . . .	3218
16.549 l4/sys/pager File Reference . . . . .	3219
16.549.1 Detailed Description . . . . .	3221
16.550 pager . . . . .	3221
16.551 l4/sys/platform_control File Reference . . . . .	3221
16.551.1 Detailed Description . . . . .	3222
16.552 platform_control . . . . .	3223
16.553 platform_control.h . . . . .	3223
16.554 platform_control.h . . . . .	3223
16.555 platform_control.h . . . . .	3224
16.556 l4/sys/platform_control.h File Reference . . . . .	3224
16.556.1 Detailed Description . . . . .	3225
16.557 platform_control.h . . . . .	3225
16.558 platform_control.h . . . . .	3227

16.559 l4/sys/rcv_endpoint File Reference . . . . .	3228
16.559.1 Detailed Description . . . . .	3229
16.560 rcv_endpoint . . . . .	3229
16.561 l4/sys/rcv_endpoint.h File Reference . . . . .	3229
16.561.1 Detailed Description . . . . .	3231
16.561.2 Enumeration Type Documentation . . . . .	3231
16.561.2.1 L4_rcv_ep_ops . . . . .	3231
16.562 rcv_endpoint.h . . . . .	3231
16.563 l4/sys/scheduler File Reference . . . . .	3232
16.563.1 Detailed Description . . . . .	3233
16.564 scheduler . . . . .	3233
16.565 l4/sys/scheduler.h File Reference . . . . .	3234
16.565.1 Detailed Description . . . . .	3236
16.566 scheduler.h . . . . .	3237
16.567 l4/sys/semaphore File Reference . . . . .	3239
16.567.1 Detailed Description . . . . .	3241
16.568 semaphore . . . . .	3241
16.569 l4/sys/semaphore.h File Reference . . . . .	3241
16.569.1 Detailed Description . . . . .	3243
16.570 semaphore.h . . . . .	3243
16.571 l4/sys/smart_capability File Reference . . . . .	3244
16.571.1 Detailed Description . . . . .	3245
16.572 smart_capability . . . . .	3245
16.573 l4/sys/snd_destination File Reference . . . . .	3247
16.573.1 Detailed Description . . . . .	3248
16.574 snd_destination . . . . .	3249
16.575 l4/sys/snd_destination.h File Reference . . . . .	3249
16.575.1 Detailed Description . . . . .	3250
16.576 snd_destination.h . . . . .	3250
16.577 l4/sys/task File Reference . . . . .	3250
16.577.1 Detailed Description . . . . .	3252
16.578 task . . . . .	3252
16.579 task.h . . . . .	3253
16.580 task.h . . . . .	3253
16.581 task.h . . . . .	3253
16.582 l4/sys/task.h File Reference . . . . .	3253
16.582.1 Detailed Description . . . . .	3254
16.583 task.h . . . . .	3255
16.584 task.h . . . . .	3257
16.585 l4/cxx/thread File Reference . . . . .	3258
16.585.1 Detailed Description . . . . .	3259
16.586 thread . . . . .	3259



16.587 l4/sys/thread File Reference . . . . .	3260
16.587.1 Detailed Description . . . . .	3261
16.588 thread . . . . .	3261
16.589 l4/sys/thread_group File Reference . . . . .	3262
16.590 thread_group . . . . .	3263
16.591 l4/sys/thread_group.h File Reference . . . . .	3264
16.592 thread_group.h . . . . .	3265
16.593 l4/sys/typeinfo_svr File Reference . . . . .	3266
16.593.1 Detailed Description . . . . .	3267
16.594 typeinfo_svr . . . . .	3267
16.595 types.h . . . . .	3268
16.596 l4/sys/types.h File Reference . . . . .	3268
16.596.1 Detailed Description . . . . .	3270
16.596.2 Typedef Documentation . . . . .	3270
16.596.2.1 l4_proto_t . . . . .	3270
16.596.2.2 l4_ret_t . . . . .	3271
16.596.3 Function Documentation . . . . .	3271
16.596.3.1 l4_capability_next() . . . . .	3271
16.597 types.h . . . . .	3271
16.598 amd64/l4/sys/arch/utcb.h File Reference . . . . .	3274
16.598.1 Detailed Description . . . . .	3275
16.599 utcb.h . . . . .	3275
16.600 arm/l4/sys/arch/utcb.h File Reference . . . . .	3276
16.600.1 Detailed Description . . . . .	3277
16.601 utcb.h . . . . .	3278
16.602 arm64/l4/sys/arch/utcb.h File Reference . . . . .	3279
16.602.1 Detailed Description . . . . .	3280
16.603 utcb.h . . . . .	3280
16.604 l4/sys/utcb.h File Reference . . . . .	3281
16.604.1 Detailed Description . . . . .	3282
16.605 utcb.h . . . . .	3283
16.606 x86/l4/sys/arch/utcb.h File Reference . . . . .	3285
16.606.1 Detailed Description . . . . .	3286
16.607 utcb.h . . . . .	3286
16.608 l4/sys/vcon File Reference . . . . .	3287
16.608.1 Detailed Description . . . . .	3289
16.609 vcon . . . . .	3289
16.610 l4/sys/vcon.h File Reference . . . . .	3289
16.610.1 Detailed Description . . . . .	3292
16.610.2 Enumeration Type Documentation . . . . .	3292
16.610.2.1 L4_vcon_read_flags . . . . .	3292
16.611 vcon.h . . . . .	3292

16.612	<a href="#">l4/sys/vcpu_context File Reference</a>	3295
16.612.1	<a href="#">Detailed Description</a>	3296
16.613	<a href="#">vcpu_context</a>	3296
16.614	<a href="#">vcpu_context.h</a>	3296
16.615	<a href="#">l4/sys/vm File Reference</a>	3296
16.615.1	<a href="#">Detailed Description</a>	3297
16.616	<a href="#">vm</a>	3298
16.617	<a href="#">l4/sys/assert.h File Reference</a>	3298
16.617.1	<a href="#">Detailed Description</a>	3299
16.617.2	<a href="#">Macro Definition Documentation</a>	3300
16.617.2.1	<a href="#">l4_assert</a>	3300
16.618	<a href="#">assert.h</a>	3300
16.619	<a href="#">l4/util/assert.h File Reference</a>	3301
16.619.1	<a href="#">Detailed Description</a>	3302
16.620	<a href="#">assert.h</a>	3302
16.621	<a href="#">atomic.h</a>	3304
16.622	<a href="#">l4/cxx/atomic.h File Reference</a>	3304
16.622.1	<a href="#">Detailed Description</a>	3305
16.623	<a href="#">atomic.h</a>	3305
16.624	<a href="#">l4/util/atomic.h File Reference</a>	3306
16.624.1	<a href="#">Detailed Description</a>	3308
16.625	<a href="#">atomic.h</a>	3309
16.626	<a href="#">l4/util/backtrace.h File Reference</a>	3313
16.626.1	<a href="#">Detailed Description</a>	3314
16.626.2	<a href="#">Function Documentation</a>	3314
16.626.2.1	<a href="#">l4util_backtrace()</a>	3314
16.627	<a href="#">backtrace.h</a>	3315
16.628	<a href="#">l4/util/base64.h File Reference</a>	3315
16.628.1	<a href="#">Detailed Description</a>	3316
16.629	<a href="#">base64.h</a>	3317
16.630	<a href="#">l4/util/bitops.h File Reference</a>	3317
16.630.1	<a href="#">Detailed Description</a>	3319
16.631	<a href="#">bitops.h</a>	3319
16.632	<a href="#">l4/util/elf.h File Reference</a>	3322
16.632.1	<a href="#">Detailed Description</a>	3328
16.633	<a href="#">elf.h</a>	3329
16.634	<a href="#">l4/util/getopt.h File Reference</a>	3339
16.634.1	<a href="#">Detailed Description</a>	3340
16.635	<a href="#">getopt.h</a>	3340
16.636	<a href="#">l4/util/keymap.h File Reference</a>	3341
16.636.1	<a href="#">Detailed Description</a>	3342
16.637	<a href="#">keymap.h</a>	3342

16.638 kip.h . . . . .	3342
16.639 kip.h . . . . .	3343
16.640 kip.h . . . . .	3343
16.641 I4/sys/kip.h File Reference . . . . .	3343
16.641.1 Detailed Description . . . . .	3344
16.641.2 Macro Definition Documentation . . . . .	3345
16.641.2.1 I4_kip_for_each_feature . . . . .	3345
16.641.3 Function Documentation . . . . .	3345
16.641.3.1 I4_kip_kernel_has_feature() . . . . .	3345
16.642 kip.h . . . . .	3346
16.643 I4/util/kip.h File Reference . . . . .	3348
16.644 kip.h . . . . .	3348
16.645 kip.h . . . . .	3349
16.646 I4/util/kprintf.h File Reference . . . . .	3349
16.646.1 Detailed Description . . . . .	3349
16.647 kprintf.h . . . . .	3350
16.648 I4/util/I4mod.h File Reference . . . . .	3350
16.648.1 Detailed Description . . . . .	3351
16.648.2 Enumeration Type Documentation . . . . .	3351
16.648.2.1 I4util_I4mod_mod_info_flag . . . . .	3351
16.649 I4mod.h . . . . .	3351
16.650 I4/util/list_alloc.h File Reference . . . . .	3352
16.650.1 Detailed Description . . . . .	3353
16.650.2 Function Documentation . . . . .	3353
16.650.2.1 I4la_alloc() . . . . .	3353
16.650.2.2 I4la_avail() . . . . .	3353
16.650.2.3 I4la_dump() . . . . .	3354
16.650.2.4 I4la_free() . . . . .	3354
16.650.2.5 I4la_init() . . . . .	3354
16.651 list_alloc.h . . . . .	3355
16.652 I4/util/lock.h File Reference . . . . .	3355
16.652.1 Detailed Description . . . . .	3356
16.653 lock.h . . . . .	3356
16.654 I4/util/mb_info.h File Reference . . . . .	3357
16.654.1 Detailed Description . . . . .	3360
16.654.2 Macro Definition Documentation . . . . .	3360
16.654.2.1 I4util_mb_for_each_mmap_entry . . . . .	3360
16.654.2.2 L4UTIL_MB_MEMORY . . . . .	3360
16.654.2.3 MB_ART_MEMORY . . . . .	3360
16.655 mb_info.h . . . . .	3361
16.656 I4/util/parse_cmd.h File Reference . . . . .	3365
16.656.1 Detailed Description . . . . .	3366

16.657	<a href="#">parse_cmd.h</a>	3366
16.658	<a href="#">printf_helpers.h</a>	3367
16.659	<a href="#">I4/util/rand.h</a> File Reference	3367
16.659.1	Detailed Description	3368
16.660	<a href="#">rand.h</a>	3368
16.661	<a href="#">I4/util/splitlog2.h</a> File Reference	3368
16.661.1	Detailed Description	3369
16.662	<a href="#">splitlog2.h</a>	3369
16.663	<a href="#">util.h</a>	3370
16.664	<a href="#">vbus</a>	3371
16.665	<a href="#">I4/vbus/vbus.h</a> File Reference	3373
16.665.1	Detailed Description	3374
16.665.2	Enumeration Type Documentation	3375
16.665.2.1	<a href="#">anonymous enum</a>	3375
16.665.2.2	<a href="#">I4vbus_icu_src_types</a>	3375
16.666	<a href="#">vbus.h</a>	3375
16.667	<a href="#">vbus_generic</a>	3376
16.668	<a href="#">vbus_gpio</a>	3377
16.669	<a href="#">vbus_gpio-ops.h</a>	3378
16.670	<a href="#">vbus_gpio.h</a>	3378
16.671	<a href="#">vbus_i2c.h</a>	3379
16.672	<a href="#">vbus_inhibitor.h</a>	3380
16.673	<a href="#">I4/vbus/vbus_interfaces.h</a> File Reference	3380
16.673.1	Detailed Description	3381
16.673.2	Typedef Documentation	3381
16.673.2.1	<a href="#">I4vbus_iface_type_t</a>	3381
16.673.3	Enumeration Type Documentation	3382
16.673.3.1	<a href="#">anonymous enum</a>	3382
16.673.3.2	<a href="#">I4vbus_iface_type_t</a>	3382
16.673.4	Function Documentation	3382
16.673.4.1	<a href="#">I4vbus_subinterface_supported()</a>	3382
16.674	<a href="#">vbus_interfaces.h</a>	3383
16.675	<a href="#">vbus_mcspi.h</a>	3383
16.676	<a href="#">vbus_pci</a>	3384
16.677	<a href="#">vbus_pci-ops.h</a>	3385
16.678	<a href="#">vbus_pci.h</a>	3385
16.679	<a href="#">vbus_pm-ops.h</a>	3386
16.680	<a href="#">vbus_pm.h</a>	3386
16.681	<a href="#">I4/vbus/vbus_types.h</a> File Reference	3386
16.681.1	Detailed Description	3388
16.681.2	Enumeration Type Documentation	3388
16.681.2.1	<a href="#">I4vbus_device_flags_t</a>	3388

16.681.2.2 l4vbus_resource_flags_t	3388
16.681.2.3 l4vbus_resource_type_t	3389
16.682 vbus_types.h	3389
16.683 vdevice-ops.h	3390
16.684 l4/vcpu/vcpu File Reference	3391
16.684.1 Detailed Description	3391
16.685 vcpu	3391
16.686 l4/sys/vcpu.h File Reference	3393
16.686.1 Detailed Description	3394
16.686.2 Function Documentation	3395
16.686.2.1 l4_vcpu_check_version()	3395
16.687 vcpu.h	3395
16.688 l4/vcpu/vcpu.h File Reference	3396
16.688.1 Detailed Description	3397
16.689 vcpu.h	3398
<b>17 Examples</b>	<b>3401</b>
17.1 hello/server/src/main.c	3401
17.2 examples/sys/ipc/ipc_example.c	3401
17.3 examples/sys/ipc/ipc.cfg	3402
17.4 examples/sys/start-with-exc/main.c	3403
17.5 examples/sys/singlestep/main.c	3405
17.6 examples/sys/aliens/main.c	3407
17.7 examples/sys/utcb-ipc/main.c	3410
17.8 examples/sys/isr/main.c	3412
17.9 examples/clntsrv/src/server.cc	3414
17.10 examples/clntsrv/src/client.cc	3415
17.11 examples/clntsrv/src/shared.h	3416
17.12 examples/clntsrv/configs/clntsrv.cfg	3416
17.13 examples/libs/l4re/c/ma+rm.c	3416
17.14 examples/libs/l4re/c++/mem_alloc/ma+rm.cc	3417
17.15 examples/libs/l4re/c++/shared_ds/ds_clnt.cc	3418
17.16 examples/libs/l4re/c++/shared_ds/ds_srv.cc	3420
17.17 examples/libs/l4re/c++/shared_ds/shared_ds.cfg	3422
17.18 examples/libs/l4re/streammap/server.cc	3423
17.19 examples/libs/l4re/streammap/client.cc	3424
17.20 examples/libs/l4re/streammap/streammap.cfg	3424
17.21 examples/libs/libirq/loop.c	3425
17.22 examples/libs/libirq/async_isr.c	3426
17.23 examples/sys/migrate/thread_migrate.cc	3426
17.24 examples/sys/migrate/thread_migrate.cfg	3428
17.25 tmpfs/lib/src/fs.cc	3428

17.26 <a href="#">examples/libs/shmc/prodcons.c</a> . . . . .	3435
<b>Index</b>	<b>3439</b>

# Chapter 1

## Overview

Welcome to the documentation of the L4Re Operating System Framework, or L4Re for short. There are two parts to this documentation: a user manual, which provides a birds eye view of L4Re and its environment, and a reference section which documents the complete programming API.

### User Manual

1. [Introduction](#) shortly explains the concept of microkernels and introduces the basic terminology.
2. [Programming for L4Re](#) explains in detail the most important programming concepts.
3. [L4Re Servers](#) provides a quick overview over standard services running on the L4Re operating system.

### Reference

The second part provides the complete reference of all classes and functions of the L4Re Operating System Framework as well as a list of example code.





# Chapter 2

## Introduction

The intention of this section is to provide a short overview about the [L4Re](#) Operating System Framework.

The general structure of a microkernel-based system will be introduced and the principal functionality of the servers in the basic environment outlined.

### 2.1 L4Re Microkernel

The [L4Re](#) Microkernel is the lowest-level component of software running in an L4Re-based system. The microkernel is the only component that runs in privileged processor mode. It does not include complex services such as program loading, device drivers, or file systems; those are implemented in user-level programs on top of it (a basic set of these services and abstractions is provided by the [L4](#) Runtime Environment).

Microkernel services are implemented in kernel objects. Tasks hold references to kernel objects in their respective *"object space"*, which is a kernel-protected table. These references are called *capabilities*. System calls to the microkernel are function invocations on kernel objects through the corresponding capabilities. These can be thought of as function invocations on object references in an object-oriented programming environment. Furthermore, if a task owns a capability, it may grant other tasks the same (or fewer) rights on this object by passing the capability from its own to the other task's object space.

From a design perspective, capabilities are a concept that enables flexibility in the system structure. A thread that invokes an object through a capability does not need to care about where this object is implemented. In fact, it is possible to implement all objects either in the kernel or in a user-level server and replace one implementation with the other transparently for clients.

#### 2.1.1 Communication

The basic communication mechanism in L4-based systems is called *"Inter Process Communication (IPC)"*. It is always synchronous, i.e. both communication partners need to actively rendezvous for IPC. In addition to transmitting arbitrary data between threads, IPC is also used to resolve hardware exceptions, faults and for virtual memory management.

### 2.1.2 Kernel Objects

The following list gives a short overview of the kernel objects provided by the [L4Re](#) Microkernel:

- **Task** A task comprises a memory address space (represented by the task's page table), an object space (holding the kernel protected capabilities), and on x86 an IO-port address space.
- **Thread** A thread is bound to a task and executes code. Multiple threads can coexist in one task and are scheduled by the microkernel's scheduler.
- **Factory** A factory is used by applications to create new kernel objects. Access to a factory is required to create any new kernel object. Factories can control and restrict object creation.
- **IPC Gate** An IPC gate is used to create a secure communication channel between different tasks. It embeds a label (kernel protected payload) that securely identifies the gate through which a message is received. The gate label is not visible to and cannot be altered by the sender.
- **IRQ** IRQ objects provide access to hardware interrupts. Additionally, programs can create new virtual interrupt objects and trigger them. This allows to implement a signaling mechanism. The receiver cannot decide whether the interrupt is a physical or virtual one.
- **Vcon** Provides access to the in-kernel debugging console (input and output). There is only one such object in the kernel and it is only available, if the kernel is built with debugging enabled. This object is typically interposed through a user-level service or without debugging in the kernel can be completely based on user-level services.
- **Scheduler** Implements scheduling policy and assignment of threads to CPUs, including CPU statistics.

## 2.2 L4Re System Structure

The system has a multi-tier architecture consisting of the following layers depicted in the figure below:

- **Microkernel** The microkernel is the component at the lowest level of the software stack. It is the only piece of software that is running in the privileged mode of the processor.
- **Tasks** Tasks are the basic containers (address spaces) in which system services and applications are executed. They run in the processor's deprivileged user mode.




Figure 2.1 Basic Structure of an L4Re based system

In terms of functionality, the system is structured as follows:

- Microkernel** The kernel provides primitives to execute programs in tasks, to enforce isolation among them, and to provide means of secure communication in order to let them cooperate. As the kernel is the most privileged, security-critical software component in the system, it is a general design goal to make it as small as possible in order to reduce its attack surface. It provides only a minimal set of mechanisms that are necessary to support applications.
- Runtime Environment** The small kernel offers a concise set of interfaces, but these are not necessarily suited for building applications directly on top of it. The [L4Re](#) Runtime Environment aims at providing more convenient abstractions for application development. It comprises low-level software components that interface directly with the microkernel. The root pager *sigma0* and the root task *Moe* are the most basic components of the [L4Re](#) Runtime Environment. Other services (e.g., for device enumeration) use interfaces provided by them.
- Applications** Applications run on top of the system and use services provided by the runtime environment – or by other applications. There may be several types of applications in the system and even virtual machine monitors and device drivers are considered applications in the terminology used in this document. They are running alongside other applications on the system.

Lending terminology from the distributed systems area, applications offering services to other applications are usually called *servers*, whereas applications using those services are named *clients*. Being in both roles is also common, for instance, a file system server may be viewed as a server with respect to clients using the file system, while the server itself may also act as a client of a hard disk driver.

## 2.3 L4Re Runtime Environment

The [L4Re](#) Runtime Environment provides a basic set of services and abstractions, which are useful to implement and run user-level applications on top of the [L4Re](#) Microkernel. They form the [L4Re](#) Operating System Framework.

The [L4Re](#) Operating System Framework consists of a set of libraries and servers. [L4Re](#) follows an object-oriented design. Server interfaces are object-oriented, and the implementation is also object-oriented.

A minimal L4Re-based application needs 3 components to be booted beforehand: the [L4Re](#) Microkernel, the root pager (Sigma0), and the root task (Moe). The Sigma0 root pager initially owns all system resources, but is usually used only to resolve page faults for the Moe root task. Moe provides the essential services to normal user applications such as an initial program loader, a region-map service for virtual memory management, and a memory (data space) allocator.

## Chapter 3

# Programming for L4Re

This part of the documentation discusses the concept of microkernel-based programming in more detail.

You should already have a basic understanding of the [L4Re](https://l4re.org/) programming environment from the tutorials available on [l4re.org](https://l4re.org/)(<https://l4re.org/>).

- [L4 Inter-Process Communication \(IPC\)](#)
- [Kernel ABI](#)
- [Capabilities and Naming](#)
- [Spaces and Mappings](#)
- [Initial Environment and Application Bootstrapping](#)
- [Memory management - Data Spaces and the Region Map](#)
- [Program Input and Output](#)
- [Initial Memory Allocator and Factory](#)
- [Application and Server Building Blocks](#)
- [Pthread Support](#)
- tasks and threads
- communication channels
- server loops
- [Interface Definition Language](#)
- hardware access
- [L4Re Build System](#)
- [Kernel Factory](#)

### 3.1 L4 Inter-Process Communication (IPC)

Inter-process communication (IPC) is the fundamental communication mechanism in the [L4Re](#) Microkernel.

Basically IPC invokes a subroutine in a different context using input and output parameters. It is used to communicate between userland threads and, as a special case, to communicate between a userland thread and a kernel object. IPC provides the only (non-debugging) way of doing system calls.

### 3.1.1 IPC mechanism

When using this API, an IPC operation can be conducted using the `l4_ipc()` function (or one of its related [helpers](#)). In general it causes a method to be invoked on the called kernel object. An IPC operation consists of a send and receive phase, but either of them can be skipped, that is, an IPC operation can consist of only either a send or a receive phase. IPC is always synchronous and blocking and can be given a timeout. Timeouts can be specified separately for each phase. Invoking the IPC syscall without any phase is deprecated.

On the lowest abstraction level, IPC operations need the following arguments:

- [flags](#) describing the IPC mode,
- the [capability selector](#) of the communication partner,
- a [label](#),
- a [message tag](#), and
- a pair of [timeout](#) values.

During an IPC operation the kernel accesses the UTCB of the current thread to read parameters which are not passed as direct arguments.

As result of an IPC operation the kernel returns a message tag and a label and the kernel also changes UTCB content. For the detailed call signature, refer to `l4_ipc()`. Furthermore, depending on the IPC parameters, the kernel might have transferred the FPU state and capabilities (memory, I/O ports, and/or object capabilities) from the sender to the receiving thread.

The transition between the IPC send phase and the IPC receive phase is atomic, that is, as soon as the send phase has finished, the thread receive phase starts. A relative receive timeout does not start before the send phase has finished (see also below) and a thread which received an IPC call from another thread can assume that the other thread is ready to receive the reply message and the replying thread can therefore reply with a timeout of zero, see [IPC Timeouts](#).

For performance optimization and under certain conditions, the kernel may perform a context switch from the IPC sender to the IPC receiver without consulting the scheduler after the send phase finished. For instance, a client performing an IPC call to a server has to wait for the server anyway. Hence, after the client request was sent to the server, the kernel switches directly to the server thread. This behavior can be disabled by setting the `L4_MSGTAG_SCHEDULE` flag in the sender message tag (see below).

#### 3.1.1.1 IPC Flags

The capability selector *flags* (`L4_SYSF_SEND`, `L4_SYSF_RECV`, `L4_SYSF_OPEN_WAIT`, `L4_SYSF_REPLY`) are used by the invoking thread to define the intended IPC operation. The variants of `l4_ipc()` (see [Object Invocation](#)) use the flags

- to request the IPC phases (send-only IPC, receive-only IPC, IPC with send and receive phase), and
- to decide, if the reply capability (see [below](#)) should be used instead of the capability of a dedicated kernel object as target for the send phase (*reply*), and
- to decide, if receiving should wait for an incoming message from any possible sender (*open wait*) instead of a message from a dedicated sender (*closed wait*).

### 3.1.1.2 Partner capability selector

The *partner capability selector* defines a kernel object as partner of the IPC operation. Some kernel objects forward IPC to a userland thread.

Basically an object capability is represented by `l4_cap_idx_t` where the bits starting from `L4_CAP_SHIFT` are used as index into the local capability table of the current address space.

Specifying `L4_INVALID_CAP` as target for an IPC operation is equivalent to specifying a thread capability of the current thread with full permissions. As a result, the userland thread either communicates with its corresponding kernel thread object (if `L4_PROTO_THREAD` is specified as protocol value, see the description of the message tag below) or the IPC target is the current userland thread. In the latter case, no IPC will be performed and the send phase and the receive phase will block until the corresponding timeout has expired, see below.

A special partner is defined by the *reply capability*. Since it would be impractical (and a security flaw) to always pass an explicit object capability to reply to for each IPC, the kernel generates an implicit one that can be used for just that purpose if the IPC contains an **open wait** phase. The reply capability is valid after a receive phase and points to the kernel object that sent the IPC just received. It can be used only once. The reply capability is selected by setting the `L4_SYSF_REPLY` flag, see above.

### 3.1.1.3 IPC Label

The IPC label is a machine word which is transferred unchanged from the IPC sender to the IPC receiver when directly sending to a userland thread. However, the primary purpose of the label is to create a relationship between an `L4::Rcv_endpoint` (`L4::lpc_gate` or `L4::lrq`) and the bound thread.

During `L4::Rcv_endpoint::bind_thread()`, a label is specified. If the thread receives an IPC message through the endpoint, that label is delivered to the receiving thread as output parameter of `l4_ipc()` instead of the label specified during the corresponding IPC send operation (see the detailed description of `L4::lpc_gate` for more details on the label with IPC gates). The label is usually used by the receiving thread to invoke the object which is responsible for handling the IPC request of the corresponding endpoint. This mechanism is used by the `L4::Epiface` mechanism for server loops.

### 3.1.1.4 IPC Message Tag

The *message tag* (`l4_msgtag_t`) describes the payload of the IPC and can also be used to enable certain features. It contains:

- a *protocol value* (cf. `l4_msgtag_t::label()`, also called the tag's *label*),
- the number of items in *UTCB message registers* to transfer (cg. `l4_msgtag_t::words()` and `l4_msgtag_t::items()`), and
- flags (cf. `l4_msgtag_t::flags()` and `L4_msgtag_flags`, may be 0).

The information from the message tag is required by the kernel to transfer the message. The IPC system call returns a message tag as result of the IPC operation. On success, a copy of the message tag specified by the sender is returned if there is a receive phase. Without receive phase, a successful IPC syscall returns the message tag specified as input parameter.

Failures during IPC are signalled using the `L4_MSGTAG_ERROR` flag in the message tag. If this bit is set by the kernel, the content of the returned message tag apart from that bit is undefined and the kernel wrote the actual error code into the `l4_thread_regs_t::error` register of the UTCB (see also *IPC Thread Control Registers*). When an IPC error occurs after the rendezvous of the IPC partners, both partners observe the same error information. If, for

instance, the IPC was aborted using `L4::Thread::ex_regs()`, the sender gets an `L4_IPC_SECANCELED` error while the receiver gets an `L4_IPC_RECANCELED` error. The function `L4Re::chkipc()` can be used to verify that an IPC operation finished successfully: It throws an error if the IPC failed.

The *protocol value* is usually used to distinguish between different protocols of the same interface. Certain protocol IDs are pre-defined when talking to kernel objects, see `L4_msgtag_protocol`. From IPC point of view, the protocol value is just payload that is transferred from sender to receiver and hence doesn't have a dedicated meaning.

By convention, during IPC calls, the protocol value is used for return values, where negative values signify errors. See the [section](#) about L4 RPC return types for further information. The function `L4Re::chksys()` can be used to verify that an RPC call using IPC was successful: It throws an error if the IPC failed or if the returned protocol value is negative.

### 3.1.1.5 IPC Timeouts

As written above, IPC *timeouts* are specified separately for the send phase (IPC send timeout) and the receive phase (IPC receive timeout). The timeout of one phase is encapsulated by `l4_timeout_s`. Both timeouts are combined into a single `l4_timeout_t` parameter. Timeouts are either relative to the current time of the invoking thread or absolute. In the latter case, the absolute time of the deadline of the respective phase is written into a UTCB buffer register (see `l4_timeout_abs()`). The relative timeout of the receive phase starts immediately after the send phase has finished.

Two specific timeout values are sufficient for most IPC operations:

- `L4_IPC_TIMEOUT_NEVER` is used if the IPC partner might not yet be ready. Usually a client trusting a server will perform an IPC call with an infinite timeout for both phases. The send phase will take some time if the IPC receiver is currently not ready. The receive phase will take some time as the server needs time to serve the request. Also, a server will usually wait with an infinite receive timeout for the next request (see below for a possible exception).
- `L4_IPC_TIMEOUT_0` is used when it is either certain that the IPC receiver is currently ready or if the IPC sender doesn't want to wait if the IPC receiver is not ready. The former case applies to a thread which was called with an IPC call, for example a server got a client request. The reply to the IPC call should use a timeout of zero to ensure that a client doesn't block a server (server could not deliver the result of the request). See also `L4::ipc_srv::Default_timeout`. Another case is an IPC send operation for waking up another thread from an IPC receive operation. If the other thread is not ready to receive, then it might be already woken up and it does not make sense to wait any longer. Also triggering an IRQ is usually done with a send timeout of 0, see `L4::Triggerable::trigger()`.

In certain cases it also makes sense to specify an IPC timeout different from "never" or "zero":

- A server might leave the server loop after some time to perform idle work (see `L4::ipc_srv::Server_iface::add_timeout()`).
- A thread does not want to wait for an infinite time if the partner is not ready. This could be also some safety measure.
- A thread wants to block for a certain amount of time without consuming CPU time. The `l4_ipc_sleep()` function specifies the `L4_INVALID_CAP` as target for an IPC receive operation and specifies the intended relative waiting period as IPC timeout. Waiting for an absolute timeout would be possible with similar code.

#### Note

The kernel IPC path is optimized for the two special cases using `L4_IPC_TIMEOUT_NEVER` and `L4_IPC_TIMEOUT_0`. Specifying a different timeout causes more maintenance effort for the kernel.

Special care is required if a finite timeout for the receive phase of an IPC call is specified: The IPC receive operation could abort before the partner was able to send the reply message. Under certain circumstances the partner may still have the temporary reply capability to the calling thread and may use this capability to reply to the caller at a later, unexpected time specifying an arbitrary IPC label. This case is relevant for servers which call another, possibly untrusted, server while serving a client request.



### 3.1.1.6 User-level Thread Control Block

The **UTCB** is located on a power-of-2-sized and power-of-2-aligned memory area shared between userland and the kernel (`L4::Task::add_ku_mem()`). The UTCB is bound to a thread during the `L4::Thread::control()` operation with the `L4::Thread::Attr` parameters set up using `L4::Thread::Attr::bind()`. The UTCB is used for IPC-related data exchange and is set up before invoking `l4_ipc()`. To access certain parts of the UTCB, the corresponding functions have to be used (there is no data type `L4_utcb` or similar). The UTCB consists of:

- the **message registers** `MR[0], MR[1], ..., MR[n-1]` with  $n = \text{L4\_UTCB\_GENERIC\_DATA\_SIZE}$  (access using `l4_utcb_mr()`),
- the **buffer descriptor register** `BDR` (access using `l4_utcb_br()`, see `l4_buf_regs_t::bdr`),
- the **buffer registers** `BR[0], BR[1], ..., BR[m-1]` with  $m = \text{L4\_UTCB\_GENERIC\_BUFFERS\_SIZE}$  (access using `l4_utcb_br()`),
- the **thread control registers** (access using `l4_utcb_tcr()`, includes the IPC error code), and
- in case of an exception IPC, the register state of the thread which triggered the exception (access using `l4_utcb_exc()`).

IPC to a kernel object requires the setup of the UTCB of the corresponding userlevel thread. IPC between userlevel threads requires the setup of UTCBs of both partners.

The kernel changes only the following UTCB content:

- The message registers of the UTCB of the receiver of an IPC, and
- the IPC error field of the thread invoking `l4_ipc()` if there was an error during IPC.

#### 3.1.1.6.1 IPC Message registers

The *message registers* contain *untyped items* and *typed items*. The sender's typed items are interpreted by the kernel in conjunction with the receiver's *receive items*. Each typed send item occupies two message registers. The untyped items, on the other hand, are free to be used by the communication partners to exchange data: The content of all message registers used for untyped items (`l4_msgtag_t::words()`) is copied from the UTCB of the IPC sender to the UTCB of the IPC receiver.

A typed send item consists of a *flexpage* (see `l4_fpage()`, `l4_obj_fpage()`, and `l4_iofpage()`) of the to be transferred capabilities (*flexpage word*) and a *message word*. There are two types of send items: *map items* and *void items*. For a void item, the message word is all zero. For a map item, the message word contains:

- the *compound bit* allowing to use the same receive buffer for the subsequent typed send item (scatter-gather behavior, see `L4_ITEM_CONT` of `l4_msg_item_consts_t`),
- the *type bit* defining this typed send item as a *map item*,
- the *grant flag* for delegating the access to the flexpage from the sender to the receiver and atomically removing the rights from the sender (see `l4_msg_item_consts_t`),
- *attributes* with semantics depending on the item type; for memory mappings, they contain cacheability information (see `l4_fpage_cacheability_opt_t`); for objects, they contain additional rights (see [Attributes and additional permissions for object send items](#)),
- the *send base* (also called *hot spot*) defining what is actually mapped when send and receive flexpages have a different size.

A typed send item can be created using `l4_sndfpage_add()`. This function sets the compound bit unconditionally. Alternatively, the functions `l4_map_control()` and `l4_map_obj_control()` can be used to set up the message word of a map item for a memory flexpage respective for objects.

See [below](#) for a description how typed items are transferred.

### 3.1.1.6.2 IPC Buffer Registers

The *buffer registers* and *buffer descriptor register* are interpreted by the kernel during the receive phase (if any). [Buffer](#) registers define *receive items* which are required to receive typed send items (memory, I/O ports or object capabilities). To specify a receive item, up to three buffer registers are required:

- A *small receive item* ([L4::ipc::Small\\_buf](#)) occupying one buffer register is sufficient to receive one object capability.
- A *receive item* ([L4::ipc::Rcv\\_fpage](#)) occupying two or three buffer registers (*message word*, a *flexpage*, and an optional destination task capability index) is required to receive memory flexpages, I/O ports, or multiple object capabilities.

### 3.1.1.6.3 IPC Buffer Descriptor Register

The buffer descriptor register defines indices of buffer registers used to receive dedicated types of send items and also contains a flag:

- 5 bits starting at [L4\\_BDR\\_MEM\\_SHIFT](#) define the index of the first receive item used for memory flexpages.
- 5 bits starting at [L4\\_BDR\\_IO\\_SHIFT](#) define the index of the first receive item used for I/O flexpages.
- 5 bits starting at [L4\\_BDR\\_OBJ\\_SHIFT](#) define the index of the first receive item used for object flexpages.
- The [L4\\_UTCB\\_INHERIT\\_FPU](#) can be set using [l4\\_utcb\\_inherit\\_fpu\(\)](#) and allows to receive the FPU state from the IPC sender. This is only relevant if the sender set [L4\\_MSGTAG\\_TRANSFER\\_FPU](#) in the message tag.

For most use cases, a BDR value of zero is sufficient. In that case, if `BR[0]` contains a void item, no capabilities are received. Otherwise, only one type of capabilities (memory, I/O ports or objects) can be received even if there are several receive items. For more complex setups that require receiving different types of capabilities in one receive operation, other BDR values are necessary.

The BDR of the receiving thread is only used by the kernel if at least one typed item is transferred during the IPC or if [L4\\_MSGTAG\\_TRANSFER\\_FPU](#) is set in the UTCB of the sending thread.

### 3.1.1.6.4 IPC Thread Control Registers

The [l4\\_thread\\_regs\\_t::error](#) register contains the IPC error code in case the [L4\\_MSGTAG\\_ERROR](#) flag is set in the message tag returned by an IPC syscall. Otherwise this register is not touched by the kernel. See [l4\\_ipc\\_tcr\\_error\\_t](#) for a detailed enumeration of all possible error codes during an IPC operation.

The [l4\\_thread\\_regs\\_t::free\\_marker](#) is set by the kernel to zero immediately before a thread is destroyed. This value indicates that the kernel does not longer use the UTCB and it can be re-used by other threads.

The other members of [l4\\_thread\\_regs\\_t](#) are never touched by the kernel.

### 3.1.1.7 Transfer of Typed Send Items

The kernel interprets all typed items in the sender UTCB ([l4\\_msgtag\\_t::items\(\)](#)) and performs the following operations while modifying the corresponding typed items in the receiver UTCB:

- If the message item of the sender is void, this item is ignored and the message word of the corresponding typed item in the receiver UTCB is set to zero (making it a void item). The flexpage word of this item is not changed.
- Otherwise, if the type bit of the message item of the sender is not set, the IPC is aborted with [L4\\_IPC\\_SEMSGCUT](#) / [L4\\_IPC\\_REMSGCUT](#).
- Otherwise, if there is a receive item corresponding to the flexpage type of the send item available (see [IPC Buffer Descriptor Register](#)), information described by the flexpage is transferred to the receiver.

In the last case, the message word of the typed item in the receiver UTCB is modified to contain the send base, the type and the size of the transferred flexpage, as well as a copy of the compound bit and the type bit of the send item. If the receiver ordered a local ID in the corresponding receive item, the kernel attempts to apply special rules, see [L4\\_RCV\\_ITEM\\_LOCAL\\_ID](#). Otherwise, regular mappings as described by the flexpage of the send item are created in the receiver space.

A receive item forms a *receive window* of a specific address and size in the receiver space. Each typed send item that is a map item requires a corresponding receive item. By default, there is a one-to-one mapping (one receive item per typed send item) but it is also possible to use one receive item to receive several typed send items: The compound bit (see [l4\\_msg\\_item\\_consts\\_t](#)) of a send item defines if the following typed send item shall use the same receive item as the current one for receiving the flexpage. If the compound bit is set, proper values of the send base shall be used to prevent overlapping of addresses in the receiver space.

The send base is relevant when the size of the receive flexpage differs from the size of the transferred resource. As a typical example, triggering a memory page fault opens a receive window covering the entire memory address space of the faulting thread. The pager will usually reply a memory flexpage smaller than the entire address space of the faulting thread. Hence, the pager has to specify a proper base which is used as offset of the sent object in the receive flexpage in the *receiver space*. If the sender flexpage is bigger than the receive window, a flexpage of the size of the receive window starting at the send base in the *sender space* is transferred to the receiver.

The kernel will stop transmission of typed items before [l4\\_msgtag\\_t::items\(\)](#) is reached either if it finds a void item as receive buffer or if the flexpage type of the send item does not match the flexpage type of the corresponding receive item. Under both conditions, the IPC is aborted with [L4\\_IPC\\_SEMSGCUT](#) / [L4\\_IPC\\_REMSGCUT](#).

#### Note

The kernel ignores the flexpage access rights of the receive items. The actual rights for a transferred resource in the target address space are defined by the access rights to that resource of the IPC sender address space and the flexpage access rights in the typed send item. Additionally, when transferring object capabilities, the transferred rights also depend on the sender's rights on the capability invoked for IPC.

The kernel does not unmap capabilities in the receive window when there is no capability present at the corresponding index at the sender. Further, the receiver cannot reliably detect at which capability indices it received capabilities in its receive windows. Therefore, before receiving from an untrusted source, all receive windows should be cleared. Otherwise the receiver may erroneously associate a capability in one of its receive windows with his last IPC partner although it was actually received in an earlier IPC.

However, the kernel indicates if at least one object capability was received or not, see [L4::lpc::Snd\\_fpage::cap\\_received\(\)](#).

## 3.1.2 Examples

A number of examples show the interplay of the concepts introduced so far.

### 3.1.2.1 User Thread to Kernel Object

The `L4::Scheduler` kernel object has a method `L4::Scheduler.idle_time()`. It takes a set of CPUs to query, represented by two machine words.

In user space, the function `L4::Cap<L4::Scheduler>->idle_time()` is called, which does the following:

- Fill `MR[0]` with a constant identifying the method being called (`L4_SCHEDULER_IDLE_TIME_OP`).
- Fill `MR[1]` and `MR[2]` with the two words making up the CPU set.
- Set up the message tag with the protocol value (`L4_PROTO_SCHEDULER`), the number of untyped and typed items (3 and 0), and some flags.
- Call `l4_ipc()` with the partner capability ID, the tag, the pointer to the filled UTCB, infinite timeouts, and with flags indicating a send and receive phase. (The label does not matter in this case.)

This function traps into kernel space using standard platform specific mechanisms. The kernel reads the protocol value on the message tag, checks that the partner capability ID refers to a valid object that speaks that protocol, and dispatches the message to the appropriate handler. The handler fills the first 64 bits of the message registers with the computed time value. This will cover `MR[0]` on 64-bit architectures and `MR[0]` and `MR[1]` on 32-bit architectures. It then sets up the return message tag:

- The number of untyped items is 1 or 2.
- The number of typed items is 0.
- The protocol value contains the return value and is set to 0.
- An error would be signalled as a negative protocol value. Under certain conditions (e.g. wrong kernel object capability specified), the error is signalled as IPC error (see `L4_MSGTAG_ERROR` in the description of the `IPC Message Tag`).
- (The return label is as irrelevant in this case as the send label.)

This reply is received by the receive phase of the original `l4_ipc()` call from userland. Finally the `l4_ipc()` function copies the time value out of the message registers and forwards it with a possible error from the message tag flags to its caller.

### 3.1.2.2 User Thread to User Thread

When the target kernel object is of type `L4::Thread` (or `L4::ipc_gate`, but we will cover this in the example [below](#)) and the message tag's protocol value is not `L4_PROTO_THREAD`, the kernel will forward the IPC message to the userland thread represented by the kernel object. There it can be received by a call to `l4_ipc()`. The restriction of the protocol number is necessary because one also wants to invoke `L4::Thread`'s control methods such as `L4::Thread.switch_to()` or `L4::Thread.ex_regs()`. Besides this restriction, the interpretation of all the IPC parameters and the untyped items of the UTCB is up to the communication partners.

### 3.1.2.2.1 Simple Messages

A simple example is a client calling a server to have a computation performed on a value: Similar to IPC from a userland thread to a kernel object, the client writes the value to `MR[0]`. It sets up the message tag with some agreed upon protocol value (which, as explained above, must be different from `L4_PROTO_THREAD`), number of untyped items to 1, typed items to 0, and no flags set. The client may want to pass a label that identifies itself, as many clients can use the server. In this context, the identifier might also be passed via the message registers, but the label is the proper place for this, as it gets a special treatment by the kernel for IPC gates (covered by the example below). The client then calls `l4_ipc()` with the tag, label and flags indicating it wants a send phase and a receive phase (as it wants a result back). The target is the capability index referring to a capability for the `L4::Thread` kernel object of the server.

To be able to receive an IPC message, the server has set up a UTCB of its own and called `l4_ipc()` with flags indicating it only wants to enter a receive phase and it accepts IPCs from any partner. This is called an **open wait**. (The alternative would be to specify a capability index referring to a `L4::Thread` capability to exclusively receive from.)

Both system calls (the send IPC initiated by the client and the receive IPC initiated by the server) may be seen by the kernel in any order but the IPC will not start before sender and receiver are ready. In that case the kernel will copy the relevant message registers the client specified in the message tag from the client's UTCB to the server's UTCB, in the current example just `MR[0]`. It will then switch the client to the receive phase of its call (which cannot yet be executed) and return the server's call with the message tag and label.

The server inspects the tag for the correct protocol value and number of untyped items passed, inspect the label to decide whether it maybe wants special treatment of this particular client, performs the computation on `MR[0]` and writes the result back to `MR[0]` (or to more words, depending on what exactly it computes). It sets up the tag in the usual way, but probably needs to pass no label, as the client knows who it is talking to.

For the reply, the server makes use the reply capability (see above). Since the client sent the last IPC to the server, the reply capability will point to it. So when the server calls `l4_ipc()` with the computed result in the message registers and using the reply capability as target, the kernel knows to forward this to the client's thread. The kernel copies the message registers from the server's UTCB to the client's UTCB, and the client's `l4_ipc()` system call, which is still stuck in the receive phase, is returned with the tag.

The client looks at the tag and then the message registers for its wanted result and the example is concluded.

### 3.1.2.2.2 Send Items

IPC between userland threads is also used to transfer typed items: Memory, I/O ports, and objects, all represented as flexpages. Typed items and untyped items can be part of the same IPC. As general rule, the sender specifies what he wants to send, the receiver where and how much it wants to receive, and the kernel checks the required permissions before doing the actual transfer. As written before, this mechanism is synchronous and the receiver cannot be transferred items against its will.

See also

[Flexpages](#)

Suppose a client wants a server to have read only access to a page of its memory. The client sets up a flexpage covering the page and with only the `L4_FPAGE_RO` right set. The server sets up a flexpage of a memory region where it will receive the mapping. This may be larger than one page, suppose for our case four pages, in which case the exact position of the mapping will be resolved by the send base provided by the sender. The client combines the hot spot and some flags into a machine word and writes it to `MR[0]` (see also `l4_map_control()`). At `MR[1]` follows the flexpage it wants to send (see also `l4_fpage()`). The server does almost the same but writes the words to `BR[0]` and `BR[1]`. (The server could also specify a hot spot, but it is currently ignored by the kernel.) The

client specifies 1 typed and 0 untyped items in the message tag. The server writes 0 to `BDR` to specify that the first receive item starts at the first buffer register.

Both client and server initiate their IPC, the client with only a send phase to the server, and the server with an open wait receive phase. The kernel checks the compatibility of the send items and the receive buffers (e.g. that no object capability flexpage is sent to a receive buffer describing a memory mapping flexpage) and updates its internal structures to reflect the change. In our case, the sender's hot spot indicates to which of the four pages that make up the receive buffer the sent page should be mapped. The kernel also translates the typed send item to the server's address space and stores it in the server's UTCB at `MR[0]` and `MR[1]`.

Once the server returns from its syscall, it will have read access to the client's shared page.

### 3.1.2.3 User Thread to User Object

A common use case for thread to thread communication is when a server implements a number of object interfaces and a client wants to invoke methods on them. For security reasons, the server does not want to hand out its thread capability to everyone it nonetheless wants to serve. It also may not want to allow every client access to everyone of its interfaces. For this purpose, IPC gates implemented by the kernel object `L4::ipc_gate` can be used. An IPC gate can be bound to a thread and forwards IPC to it. In doing so it applies two transformations

1. It sets the label to a predefined value.
2. It changes the rights of transferred items (see `L4_CAP_FPAGE_S`).

For each object of every interface the server implements, it creates an IPC gate and binds it to itself (see `L4::ipc_gate::bind_thread()`). It sets the gate's label to a unique value identifying the object. Then it hands the gate out to clients. Several clients can be handed the same gate and will all end up invoking methods on the same object.

Instead of setting the target as the server's thread kernel object, the client uses the IPC gate's instead. The label the client sends is irrelevant, as the gate will overwrite it with the value the server has set during the bind operation. The server executes an open wait, and the kernel performs the same operation as in the above [example](#) with the transformed IPC finally ending up in the server's thread.

The server checks that the received label refers to one of its objects. It then checks if the protocol value in the message tag matches the interface the object implements. Then it invokes the method specified in `MR[0]` with the rest of the arguments. Finally it returns the results via UTCB and message tag to the reply capability and waits for the next IPC.

## 3.2 Kernel ABI

This section details the binary representation of the IPC interface of the kernel.

It accompanies the [L4 Inter-Process Communication \(IPC\)](#) section. The details presented here are usually not relevant when developing L4Re applications and can therefore be skipped by many readers.

### Note

The kernel ABI is subject to change. Please use the API instead of relying on particular binary representations.

The following notation is used to indicate how particular data fields are used:


- `[in]`: The kernel reads and interprets this field.
- `[out]`: The kernel writes this field with information provided by the kernel.
- `[cpy]`: The kernel copies this field from sender to receiver (without interpretation if `[in]` is not listed as well).

The above indications may be combined.

### 3.2.1 Capability selector and flags

See [partner capability selector](#) and [IPC flags](#).

The kernel reads and interprets all the fields ([in]).




- Bits 0...3 [in]: These bits correspond to the capability selector flags. The individual bits correspond to [L4\\_SYSF\\_REPLY](#), [L4\\_SYSF\\_OPEN\\_WAIT](#), [L4\\_SYSF\\_RECV](#), [L4\\_SYSF\\_SEND](#). Note that not all combinations of those bits are valid; see [L4\\_SYSF\\_NONE](#) for an overview.
- Bits 4...10 [in] SBZ: should be zero
- Bit 11 [in] special: Set when using [L4\\_INVALID\\_CAP](#), otherwise unset.
- Bits 12...MSB [in]: Capability index if special is unset, otherwise all those bits should be one (see [L4\\_INVALID\\_CAP](#), [partner capability selector](#) and [l4\\_cap\\_idx\\_t](#)).

### 3.2.2 Label

See [IPC label](#).


When IPC is sent via a thread capability, the label is copied to the receiver unchanged ([cpy]).

When IPC is sent via an IPC gate, the sent label is ignored and the kernel provides the bitwise OR (|) of the IPC gate label and the sender's write and special permissions (see [L4\\_CAP\\_FPAGE\\_W](#) and [L4\\_CAP\\_FPAGE\\_S](#)) of the used capability ([out]):



### 3.2.3 Message tag

See [IPC message tag](#). Note that, for a message tag returned by the kernel, if the error flag is set, all other contents of the message tag is undefined.



- Bits 0...5 [in,cpy] `words`: Number of (untyped) message words in the UTCB's message registers. See [l4\\_msgtag\\_words\(\)](#) and [l4\\_msgtag\\_t::words\(\)](#).
- Bits 6...11 [in,cpy] `items`: Number of typed message items in the UTCB's message registers. See [l4\\_msgtag\\_items\(\)](#) and [l4\\_msgtag\\_t::items\(\)](#).
- Bit 12 [in,cpy] `transfer` FPU flag: See [L4\\_MSGTAG\\_TRANSFER\\_FPU](#).
- Bit 13 [in,cpy] `schedule` flag: See [L4\\_MSGTAG\\_SCHEDULE](#).
- Bit 14 SBZ: should be zero
- Bit 15 [out] `error`: See [L4\\_MSGTAG\\_ERROR](#), [l4\\_msgtag\\_has\\_error\(\)](#) and [l4\\_msgtag\\_t::has\\_error\(\)](#).
- Bits 16...MSB [cpy] `payload`: Transferred to receiver unchanged; not interpreted by kernel (unless it is the communication partner). For IPC calls or send-only IPC, this is usually the protocol. For replies, this is usually used for return values and server error signaling. See [l4\\_msgtag\\_label\(\)](#) and [l4\\_msgtag\\_t::label\(\)](#).

### 3.2.4 Timeouts

See [IPC timeouts](#) and [l4\\_timeout\\_t](#).

The kernel reads and interprets all the fields ([in]).

```

31      [16]      16 15      [16]      0  bits
|-----|-----|
|      [in]      |      [in]      |
| send timeout  | receive timeout |
|-----|-----|

```

A timeout has the following format. There are two special timeout values:

- *Zero timeout*: Only bit 10 is set. See [L4\\_IPC\\_TIMEOUT\\_0](#).

```

15  [5]  11  10   9      [10]      0  bits
|-----|-----|-----|
|      0      |  1  |      0      |
|-----|-----|-----|

```

- *Infinite timeout*: All bits are unset. See [L4\\_IPC\\_TIMEOUT\\_NEVER](#).

```

15      [16]      0  bits
|-----|
|      0      |
|-----|

```

Otherwise, the timeout is either relative or absolute, which is specified by bit 15.

- *Relative timeout*: If bit 15 is unset, the timeout is `mantissa * 2 ^ exponent` micro seconds relative to the current time. The `mantissa` must not be zero:

```

15  14  [5]  10  9      [10]      0  bits
|----|-----|-----|
|  0  | exponent | mantissa ≠ 0  |
|----|-----|-----|

```

- *Absolute timeout*: If bit 15 is set, an absolute timeout is specified in the UTCB's buffer registers starting at `buf reg idx` (the particular number of registers depends on the architecture; see [l4\\_timeout\\_s](#)):

```


15  14      [9]      6 5      [6]      0  bits
|----|-----|-----|
|  1  |      SBZ      | buf reg idx |
|----|-----|-----|

```



### 3.2.5 User-level thread control block (UTCB)


See [User-level thread control block \(UTCB\)](#).



- Words 0...62 MRs: See [IPC Message registers](#) and [l4\\_utcb\\_mr\(\)](#). The number of message registers is defined by [L4\\_UTCB\\_GENERIC\\_DATA\\_SIZE](#). The actually used message registers are defined by `words` and `items` in the [message tag](#). The layout of a typed message item varies depending on being an input or output value, see [typed message items](#).
- Word 63 [(out)]: Depending on the architecture, this word may be used by the kernel to signify the position of a thread's UTCB in memory. See architecture-specific implementation of [l4\\_utcb\(\)](#). If at all, the kernel writes this word when kernel-user memory is set up as UTCB while binding a thread to a task; see [l4\\_thread\\_control\\_bind\(\)](#), [L4::Thread::Attr::bind\(\)](#).
- Word 64 [in] BDR: See [buffer descriptor register](#).
- Words 65...122 [in] BRs: See [IPC Buffer Registers](#), [receive items](#) and [l4\\_utcb\\_br\(\)->br](#). The number of buffer registers is defined by [L4\\_UTCB\\_GENERIC\\_BUFFERS\\_SIZE](#).
- Word 123 [out] `error code`: See [IPC Thread Control Registers](#) and [l4\\_utcb\\_tcr\(\)->error](#).
- Word 124 [(out)] `free marker`: Written by the kernel, but not necessarily during IPC. See [IPC Thread Control Registers](#) and [l4\\_utcb\\_tcr\(\)->free\\_marker](#).
- Word 125...128 TLS: Ignored and left untouched by the kernel. See [IPC Thread Control Registers](#) and [l4\\_utcb\\_tcr\(\)->user](#).

#### 3.2.5.1 Buffer descriptor register


See [IPC Buffer Descriptor Register](#) and [l4\\_utcb\\_br\(\)->bdr](#).



### 3.2.6 Typed message items

The number of words in a typed message item varies depending on the particular kind of item. However, for the first word, the following properties are shared:

- *Void item*: If all bits of the first word of a typed message item are zero, then it is a void item.
- *Non-void item*: The first word of a non-void typed message item has the following binary layout:



Bit 3 ( $t$ ) is the type bit. If  $t$  is set, the item is a map item. Currently, map item is the only supported type. Hence, this bit must be set for all items except for void items.


There are three sub-types of typed message items: *send items*, *receive items*, and *return items*; see [Message Items](#).

Many typed items make use of flexpages, therefore, these are described before the various kinds of typed items. Note that flexpages are also used outside of typed message items, e.g., for [L4::Task::unmap\(\)](#).

#### 3.2.6.1 Flexpages

A flexpage consists of a single word and, except for some special values, describes a range in an address space, see [flex pages](#).


The general layout is defined as follows:



- Bits 4...5 type: See [l4\\_fpage\\_type\(\)](#) and [L4\\_fpage\\_type](#).

The type [L4\\_FPAGE\\_SPECIAL](#) only supports some selected values, which are only supported for selected interfaces; see [L4\\_FPAGE\\_SPECIAL](#).

The other types share the same layout:




- Bits 0...3 permissions: See [l4\\_fpage\\_rights\(\)](#), [L4\\_fpage\\_rights](#) (memory space) and [L4\\_cap\\_fpage\\_rights](#) (object space). Should be zero for I/O port space.
- Bits 6...11 order: The  $\log_2$  size of the flexpage. See [l4\\_fpage\\_size](#).
- Bits 12...MSB start: The starting page number / I/O port number / capability index of the flexpage. Must be aligned to the flexpage size. See [l4\\_fpage\\_page\(\)](#), [l4\\_fpage\\_memaddr\(\)](#), [l4\\_fpage\\_ioport\(\)](#) and [l4\\_fpage\\_obj\(\)](#).

Also see [l4\\_fpage\(\)](#) (memory space), [l4\\_iofpage\(\)](#) (I/O port space) and [l4\\_fpage\\_obj\(\)](#) (object space).

### 3.2.6.2 Send items

A send item consists of two words. The second word of a non-void send item is a [flexpage](#). The type of the flexpage determines the interpretation of the `attr` bits in the first word (see below).

If not void, the layout of the first word is defined as follows:



SBZ means “should be zero”.


- Bit 0 (compound): Compound bit. See [L4\\_ITEM\\_CONT](#) and [L4::ipc::Snd\\_fpage::is\\_compound\(\)](#).
- Bit 1 (grant): Grant flag. See [L4\\_ITEM\\_MAP](#), [L4\\_MAP\\_ITEM\\_GRANT](#) and [L4::ipc::Snd\\_fpage::Map\\_type](#).
- Bits 7..4 (attr): Attributes. See [Attributes and additional permissions for object send items](#) and [l4\\_fpage\\_cacheability\\_opt\\_t](#), [L4::ipc::Snd\\_fpage::Cacheopt](#).
- Bits MSB..12 (hot\_spot): Send base (also called hot spot). See [L4::ipc::Snd\\_fpage::snd\\_base\(\)](#).

For details, see [IPC Message registers](#).

### 3.2.6.3 Receive items


A non-void receive item consists of up to three words.

If not void, the general layout of the first word is defined as follows:




The `small` and `fwd` bits determine the details of the layout of the whole message item.

If `small` is unset, then also `rcv_id` must be unset, and the most significant bits should be zero:



If `small` is set, the most significant bits are layouted as follows:





```

|-----|-----|-----|---|-----|---|-----|
| hot_spot | order | type | 1 | 01 | c | | undefined |
|_-----|_-----|_-----|_--|_-----|_--|_-----|

```

10: Used if the receive item's `rcv_id` bit was set and the conditions for transferring an IPC gate label were fulfilled. In that case, no mapping is done for this item and the payload consists of the bitwise OR (|) of the IPC gate label and the write and special permissions (see [L4\\_CAP\\_FPAGE\\_W](#) and [L4\\_CAP\\_FPAGE\\_S](#)) that would have been mapped (also see [L4::lpc::Snd\\_fpage::id\\_received\(\)](#)):

```

                                     2 1      0 bits
|-----|-----|-----|---|-----|---|-----|
| hot_spot | order | type | 1 | 10 | c | | label | rights |
|_-----|_-----|_-----|_--|_-----|_--|_-----|

```

11: Used if the receive item's `rcv_id` bit was set and the conditions for transferring the sender's flexpage word were fulfilled. In that case, no mapping is done for this item and the payload is a copy of the sender's flexpage word (also see [L4::lpc::Snd\\_fpage::local\\_id\\_received\(\)](#)):

```

|-----|-----|-----|---|-----|---|-----|
| hot_spot | order | type | 1 | 11 | c | | send flexpage |
|_-----|_-----|_-----|_--|_-----|_--|_-----|


```

### 3.3 Capabilities and Naming

The [L4Re](#) system is a capability based system which uses and offers capabilities to implement fine-grained access control.

Generally, owning a capability means to be allowed to communicate with the object the capability points to. All user-visible kernel objects, such as tasks, threads, and IRQs, can only be accessed through a capability. Please refer to the [Kernel Objects](#) documentation for details. Capabilities are stored in per-task capability tables (the object space) and are referenced by capability selectors or object flexpages. In a simplified view, a capability selector is a natural number indexing into the capability table of the current task.

As a matter of fact, a system designed solely based on capabilities uses so-called 'local names' because each task can only access those objects made available to this task. Other objects are not visible to and accessible by the task.



**Figure 3.1 Capabilities and Local Naming in L4**

So how does an application get access to a service? In general all applications are started with an initial set of available objects. This set of objects is predetermined by the creator of a new application process and granted directly to the new task before starting the first application thread. The application can then use these initial objects to request access to further objects or to transfer capabilities to its own objects to other applications. A central L4Re object for exchanging capabilities at runtime is the name-space object, implementing a store of named capabilities.

From a security perspective, the set of initial capabilities (access rights to objects) completely define the execution environment of an application. Mandatory security policies can be defined by well known properties of the initial objects and carefully handled access rights to them.

### 3.4 Spaces and Mappings

Each task in the L4Re system has access to two resource spaces (three on IA32) which are maintained by the kernel.

These are the

1. object space,
2. memory space, and
3. IO-port space (only on IA32).

The entities addressed in each space are capabilities to objects, virtual memory pages, and IO ports. The addresses are unsigned integers and the largest valid address depends on which space is referenced, the hardware, and the configuration of the kernel. Although a program can access memory at byte granularity, from the kernel's point of view the address granularity in the memory space is not bytes but pages, as determined by the hardware. The address of a capability is also called its "capability slot".

Flexpages describe a range in any of the spaces that has a power-of-two length and is also aligned to this length. They additionally hold access rights information and further space specific information.

When a resource is present at some address in a task's corresponding resource space, then we say that resource is mapped to that task. For example, a capability to the task's main thread may be mapped to capability slot 5, or the first page of the code segment a thread executes is mapped to virtual memory page 12345. However, there need not be any resource mapped to an address.

Tasks can exchange resources through a process called "mapping" during IPC and using the [L4::Task::map\(\)](#) method. The sending task specifies a send flexpage and the receiving task a receive flexpage. The resources mapped to the send flexpage will then be mapped to the receive flexpage by the kernel.

Memory mappings and IO port mappings are hierarchical: If a resource of such a type is subject of a map operation, the received mapping is a child mapping of the corresponding mapping in the sending task (parent mapping). The kernel usually respects the relationship between these two mappings (granting is an exception; see below): If rights of a parent mapping are revoked using [L4::Task::unmap\(\)](#), these rights are also removed from its child mappings. Also, if a mapping is completely removed (via [L4::Task::unmap\(\)](#) or by mapping something else at its place), then also all child mappings are removed. In contrast, revoking rights of a child mapping leaves the rights of its parent mapping untouched.

The mapping of a resource can be performed as *grant* operation (see [L4\\_MAP\\_ITEM\\_GRANT](#)): Such an operation includes the removal of all involved mappings from the send flexpage (basically a move operation). While with a map operation without grant the mapping in the send flexpage remains the parent of all child mappings (including the new child mapping in the receive flexpage), a grant operation moves the mappings covered by the send flexpage to the corresponding addresses from the receive flexpage while leaving the parent/child relationship of the moved mappings with other mappings untouched.

During a map operation at most the access rights of the source mapping(s) can be transferred but no additional rights can be added. So only rights that are present in the source mapping and that are specified in the send item/flexpage are transferred. This also holds for grant mappings, however, rights revocation is *not* guaranteed to be applied to descendant mappings in case of grant.

There are cases where a grant operation is not or cannot be performed as requested; see [L4\\_MAP\\_ITEM\\_GRANT](#) for details.

Object capabilities are not hierarchical – they have no children. The result of the map operation on an object capability is a copy of that capability in the object space of the destination task.

## 3.5 Initial Environment and Application Bootstrapping

New applications that are started by a loader conforming to [L4Re](#) get provided an [Initial Environment](#).

This environment comprises a set of capabilities to initial [L4Re](#) objects that are required to bootstrap and run this application. These capabilities include:

- A capability to an initial memory allocator for obtaining memory in the form of data spaces
- A capability to a factory which can be used to create additional kernel objects
- A capability to a Vcon object for debugging output and maybe input

- A set of named capabilities to application specific objects

During the bootstrapping of the application, the loader establishes data spaces for each individual region in the ELF binary. These include data spaces for the code and data sections, and a data space backed with RAM for the stack of the program's first thread.

One loader implementation is the `moe` root task. Moe usually starts an *init* process that is responsible for coordinating the further boot process. The default *init* process is `ned`, which implements a script-based configuration and startup of other processes. Ned uses Lua (<https://www.lua.org>) as its scripting language, see [Ned Script example](#) for more details.

### 3.5.1 Configuring an application before startup

The default L4Re init process (Ned) provides a Lua script based configuration of initial capabilities and application startup. Ned itself also has a set of initial objects available that can be used to create the environment for an application. The most important object is a kernel object factory that allows creation of kernel objects such as IPC gates (communication channels), tasks, threads, etc. Ned uses Lua tables (associative arrays) to represent sets of capabilities that shall be granted to application processes.

```
local caps = {
    name = some_capability
}
```

The L4 Lua package in Ned also has support functions to create application tasks, region-map objects, etc. to start an ELF binary in a new task. The package also contains Lua bindings for basic L4Re objects, for example, to generic factory objects, which are used to create kernel objects and also user-level objects provided by user-level servers.

```
L4.default_loader:start({ caps = { some_service = service } }, "rom/program --arg");
```

### 3.5.2 Connecting clients and servers

In general, a connection between a client and a server is represented by a communication channel (IPC gate) that is available to both of them. You can see the simplest connection between a client and a server in the following example.

```
local loader = L4.default_loader; -- which is Moe
local svc = loader:new_channel(); -- create an IPC gate
loader:start({ caps = { service = svc:svr() } }, "rom/my_server");
loader:start({ caps = { service = svc:m("rw") } }, "rom/my_client");
```

As you can see in the snippet, the first action is to create a new channel (IPC gate) using `loader:new_channel()`. The capability to the gate is stored in the variable `svc`. Then the binary `my_server` is started in a new task, and full (`:svr()`) access to the IPC gate is granted to the server as initial object. The gate is accessible to the server application as "service" in the set of its initial capabilities. Virtually in parallel a second task, running the client application, is started and also given access to the IPC gate with less rights (`:m("rw")`), note, this is essential). The server can now receive messages via the IPC gate and provide some service and the client can call operations on the IPC gate to communicate with the server.

Services that keep client specific state need to implement per-client server objects. Usually it is the responsibility of some authority (e.g., Ned) to request such an object from the service via a generic factory object that the service provides initially.

```
local loader = L4.default_loader; -- which is Moe
local svc = loader:new_channel():m("rws"); -- create an IPC gate with rws rights
loader:start({ caps = { service = svc:svr() } }, "rom/my-service");
loader:start({ caps = { foo_service = svc:create(object_to_create, "param") } }, "rom/client");
```

This example is quite similar to the first one, however, the difference is that Ned itself calls the `create` method on the factory object provided by the server and passes the returned capability of that request as "foo\_service" to the client process.

#### Note

The `svc:create(...)` call blocks on the server. This means the script execution blocks until the my-service application handles the create request.



## 3.6 Memory management - Data Spaces and the Region Map

### 3.6.1 User-level paging

Memory management in L4-based systems is done by user-level applications, the role is usually called *pager*. Tasks can give other tasks full or restricted access rights to parts of their own memory. The kernel offers means to give access to memory in a secure way, often referred to as *memory mapping*.

The mapping mechanism allows one task to resolve page faults of another: A thread usually has a pager assigned to it. When the thread causes a page fault, the kernel sends an IPC message to the pager with information about the page fault. The pager answers this IPC by either providing a backing page, or with an error. The kernel will map the backing page into the address space of the faulting thread's task.

These mechanisms can be used to construct a memory and paging hierarchy among tasks. The root of the hierarchy is `sigma0`, which initially gets all system resources and hands them out once on a first-come-first-served basis. Memory resources can be mapped between tasks at a page-size granularity. This size is predetermined by the CPU's memory management unit and is commonly set to 4 kB.

#### 3.6.1.1 Data spaces

A data space is the [L4Re](#) abstraction for objects which may be accessed in a memory mapped fashion (i.e., using normal memory read and write instructions). Examples include the sections of a binary which the loader attaches to the application's address space, files in the ROM or on disk provided by a file server, the registers of memory-mapped devices and anonymous memory such as the heap or the stack.

Anonymous memory data spaces in particular (but in general all data spaces except memory mapped IO) can either be constructed entirely from a portion of the RAM or the current working set may be multiplexed on some portion of the RAM. In the first case it is possible to eagerly insert all pages (more precisely page-frame capabilities) into the application's address space such that no further page faults occur when this data space is accessed. In general, however, only the pages for some portion are provided and further pages are inserted by the pager as a result of page faults.

#### 3.6.1.2 Virtual Memory Handling

The virtual memory of each task is constructed from data spaces backing virtual memory regions (VMRs). The management of the VMRs is provided by an object called *region map*. A dedicated region-map object is associated with each task; it allows attaching and detaching data spaces to an address space as well as reserving areas of virtual memory. Since the region-map object possesses all knowledge about the virtual memory layout of a task, it also serves as an application's default pager.

#### 3.6.1.3 Memory Allocation

Operating systems commonly use anonymous memory for implementing dynamic memory allocation (e.g., using `malloc` or `new`). In an L4Re-based system, each task gets assigned a memory allocator providing anonymous memory using data spaces.

See also

[L4Re::Dataspace](#) and [L4Re::Rm](#).

## 3.7 Program Input and Output

The initial environment provides a Vcon capability used as the standard input/output stream.

Output is usually connected to the parent of the program and displayed as debugging output. The standard output is also used as a back end to the C-style printf functions and the C++ streams.

Vcon services are implemented in Moe and the loader as well as by the [L4Re](#) Microkernel and connected either to the serial line or to the screen if available.

See also

[Virtual Console](#)

## 3.8 Initial Memory Allocator and Factory

The purpose of the memory allocator and of the factory is to provide the application with the means to allocate memory (in the form of data spaces) and kernel objects respectively.

An initial memory allocator and an initial factory are accessible via the initial [L4Re](#) environment.

See also

[L4Re::Mem\\_alloc](#)

The factory is a kernel object that provides the ability to create new kernel objects dynamically. A factory imposes a resource limit for kernel memory, and is thus a means to prevent denial of service attacks on kernel resources. A factory can also be used to create new factory objects.

See also

[Factory](#)

## 3.9 Application and Server Building Blocks

So far we have discussed the environment of applications in which a single thread runs and which may invoke services provided through their initial objects.

In the following we describe some building blocks to extend the application in various dimensions and to eventually implement a server which implements user-level objects that may in turn be accessed by other applications and servers.

### 3.9.1 Creating Additional Application Threads

To create application threads, one must allocate a stack on which this thread may execute, create a thread kernel object and setup the information required at startup time (instruction pointer, stack pointer, etc.). In [L4Re](#) this functionality is encapsulated in the pthread library.

### 3.9.2 Providing a Service

In capability systems, services are typically provided by transferring a capability to those applications that are authorised to access the object to which the capability refers to.

Let us discuss an example to illustrate how two parties can communicate with each other: Assume a simple file server, which implements an interface for accessing individual files: `read(pos, buf, length)` and `write(pos, data, length)`.

L4Re provides support for building servers based on the class `L4::Server_object`. `L4::Server_object` provides an abstract interface to be used with the `L4::Server` class. Specific server objects such as, in our case, files inherit from `L4::Server_object`. Let us call this class `File_object`. When invoked upon receiving a message, the `L4::Server` will automatically identify the corresponding server object based on the capability that has been provided to its clients and invoke this object's `dispatch` function with the incoming message as a parameter. Based on this message, the server must then decide which of the protocols it implements was invoked (if any). Usually, it will evaluate a protocol specific opcode that clients are required to transmit as one of the first words in the message. For example, assume our server assigns the following opcodes: `Read = 0` and `Write = 1`. The `dispatch` function calls the corresponding server function (i.e., `File_object::read()` or `File_object::write()`), which will in turn parse additional parameters given to the function. In our case, this would be the position and the amount of data to be read or written. In case the write function was called the server will now update the contents of the file with the data supplied. In case of a read it will store the requested part of the file in the message buffer. A reply to the client finishes the client request.

## 3.10 Pthread Support

L4Re supports the standard pthread library functionality.

Therefore L4Re itself does not contain any documentation for pthreads itself. Please refer to the standard pthread documentation instead.

The L4Re specific parts will be described herein.

- Include pthread-l4.h header file:

```
#include <pthread-l4.h>
```

- Return the local thread capability of a pthread thread:

Use `pthread_l4_cap(pthread_t t)` to get the capability index of the pthread `t`.

For example:

```
pthread_l4_cap(pthread_self());
```

- Setting the L4 priority of an L4 thread works with a special scheduling policy (other policies do not affect the L4 thread priority):

```
pthread_t t;
pthread_attr_t a;
struct sched_param sp;

pthread_attr_init(&a);
sp.sched_priority = l4_priority;
pthread_attr_setschedpolicy(&a, SCHED_L4);
pthread_attr_setschedparam(&a, &sp);
pthread_attr_setinheritsched(&a, PTHREAD_EXPLICIT_SCHED);

if (pthread_create(&t, &a, pthread_func, NULL))
    // failure...

pthread_attr_destroy(&a);
```

- You can prevent your pthread from running immediately after the call to `pthread_create(..)` by adding `PTHREAD_L4_ATTR_NO_START` to the `create_flags` of the pthread attributes. To finally start the thread you need to call `scheduler()->run_thread()` passing the capability of the pthread and scheduling parameters.

```
pthread_t t;
pthread_attr_t attr;

pthread_attr_init(&attr);
attr.create_flags |= PTHREAD_L4_ATTR_NO_START;

if (pthread_create(&t, &attr, pthread_func, nullptr))
    // failure...

pthread_attr_destroy(&attr);

// do stuff

auto ret = L4Re::Env::env()->scheduler()->run_thread(pthread_l4_cap(t),
                                                    l4_sched_param(2));
if (l4_error(ret))
    // failure...
```

### Constraints on pthread\_t, user-land capability slot, and kernel thread-object

- `pthread_l4_cap()` is guaranteed to return the valid capability slot of the pthread (A) until `pthread_join()` or `pthread_detach()` is invoked on (A)'s `pthread_t`.
- `pthread_l4_cap()` exposes internal state of the pthread management, take the necessary precautions as you would for any shared data in concurrent environments. If you use `pthread_l4_cap()` guarding against concurrency issues is your duty.
- There is no guarantee that a valid capability slot points to a present capability.

#### • Example

It is possible to obtain a valid thread capability slot and for `l4_task_cap_valid()` to return the capability as not present. The following example showcases a possible sequence of events.

```
// Assume: void some_func(void *)
pthread_t pthread = nullptr;
pthread_create(&pthread, nullptr, some_func, nullptr);

// pthread running some_func()
l4_cap_idx_t cap_idx = pthread_l4_cap(pthread);
l4_is_valid_cap(cap_idx); // --> true

long valid = l4_task_cap_valid(L4RE_THIS_TASK_CAP, cap_idx).label();
// valid == 1 --> capability object is present (refers to a kernel object).

// some_func() exits

cap_idx = pthread_l4_cap(pthread);
l4_is_valid_cap(cap_idx); // --> true

valid = l4_task_cap_valid(L4RE_THIS_TASK_CAP, cap_idx).label();
// valid == 0 --> capability object is not present (refers to no kernel object).

pthread_join(pthread, nullptr); // invalidates the cap slot and frees
                                // the pthread's data structures

// using cap_idx here is undefined behavior.
```

## 3.11 Interface Definition Language

An interface definition in L4Re is normally declared as a class derived from `L4::Kobject_t`.

For example, the [simple calculator example](#) declares its interface like that:

```
struct Calc : L4::Kobject_t<Calc, L4::Kobject>
{
```

```

L4_INLINE_RPC(long, sub, (l4_uint32_t a, l4_uint32_t b, l4_uint32_t *res));
L4_INLINE_RPC(long, neg, (l4_uint32_t a, l4_uint32_t *res));

typedef L4::Typeid::Rpc<sub_t, neg_t> Rpc;
};

```

The signature of each function is first declared using one of the RPC macros (see below) and then all the functions need to be listed in the `Rpcs` type.

Clients invoke these functions with the name given to the RPC macros, `sub` and `neg` above. Servers implement them by defining functions with an `op_` prepended, `op_sub` and `op_neg`. The types of the parameters in the macro definition, on the server side, and on the client side are not the same. The following section describes how they are related to each other.

### 3.11.1 Parameter types for RPC

Generally all value parameters, const reference parameters, and const pointer parameters to an RPC interface are considered as input parameters for the RPC and are transmitted from the client to the server.

#### Note

This means that `char const *` is treated as an input `char` and not as a zero terminated string value, for strings see `L4::lpc::String<>`.

Parameters that are non-const references or non-const pointers are treated as output parameters going from the server to the client.

There are special data types that appear on only one side (client or server) when used, see the following table for details.

```
L4_RPC(l4_ret_t, test, (int arg1, char const *arg2, unsigned *ret1));
```

The example shows the declaration of a method called `test` with `l4_ret_t` as return type, `arg1` is an `int` input, `arg2` a `char` input, and `ret1` an unsigned output parameter.

Type	Direction	Client-Type	Server-Type
T	Input	T	T
T const &	Input	T const &	T const &
T const *	Input	T const *	T const &
T &	Output	T &	T &
T *	Output	T *	T &
<a href="#">L4::Ipc::In_out&lt;T &amp;&gt;</a>	In/Out	T &	T &
<a href="#">L4::Ipc::In_out&lt;T *&gt;</a>	In/Out	T *	T &
<a href="#">L4::Ipc::Cap&lt;T&gt;</a>	Input	<a href="#">L4::Ipc::Cap&lt;T&gt;</a>	<a href="#">L4::Ipc::Snd_fpage</a>
<a href="#">L4::Ipc::Out&lt;L4::Cap&lt;T&gt;&gt;</a>	Output	<a href="#">L4::Cap&lt;T&gt;</a>	<a href="#">L4::Ipc::Cap&lt;T&gt; &amp;</a>
<a href="#">L4::Ipc::Rcv_fpage</a>	Input	<a href="#">L4::Ipc::Rcv_fpage</a>	void
<a href="#">L4::Ipc::Small_buf</a>	Input	<a href="#">L4::Ipc::Small_buf</a>	void

Array types can be used to transmit arrays of variable length. They can either be stored in a client-provided buffer ([L4::lpc::Array](#)), copied into a server-provided buffer ([L4::lpc::Array\\_in\\_buf](#)) or directly read and written into the UTCB ([L4::lpc::Array\\_ref](#)).

Constraints on [L4::lpc::Array\\_ref](#):

- the start position of this array type needs to be known in advance.
- it must be the last parameter of a message.
- the size of the array type is not transmitted to the server, only the client side knows the intended size of the input array. The server assumes the rest of the UTCB as the actual array. Different sever-side behavior must be steered otherwise, e.g. through another parameter.

Type	Direction	Client-Type	Server-Type
<code>L4::Ipc::Array&lt;const T&gt;</code>	Input	<code>L4::Ipc::Array&lt;const T&gt;</code>	<code>L4::Ipc::Array_ref&lt;const T&gt;</code>
<code>L4::Ipc::Array&lt;const T&gt;</code>	Input	<code>L4::Ipc::Array&lt;const T&gt;</code>	<code>L4::Ipc::Array_in_buf&lt;const T&gt;</code>
<code>L4::Ipc::Array&lt;T&gt; &amp;</code>	Output	<code>L4::Ipc::Array&lt;T&gt; &amp;</code>	<code>L4::Ipc::Array_ref&lt;T&gt; &amp;</code>
<code>L4::Ipc::Array_ref&lt;T&gt; &amp;</code>	Output	<code>L4::Ipc::Array_ref&lt;T&gt; &amp;</code>	<code>L4::Ipc::Array_ref&lt;T&gt; &amp;</code>

Finally, there are some optional types where the sender can choose if the parameter should be included in the message. These types are for the implementation of some legacy message formats and should generally not be needed for the definition of ordinary interfaces.

Type	Direction	Client-Type	Server-Type
<code>L4::Ipc::Opt&lt;T&gt;</code>	Input	<code>L4::Ipc::Opt&lt;T&gt;</code>	<code>T</code>
<code>L4::Ipc::Opt&lt;const T*&gt;</code>	Input	<code>L4::Ipc::Opt&lt;const T*&gt;</code>	<code>T</code>
<code>L4::Ipc::Opt&lt;T &amp;&gt;</code>	Output	<code>T &amp;</code>	<code>L4::Ipc::Opt&lt;T&gt; &amp;</code>
<code>L4::Ipc::Opt&lt;T *&gt;</code>	Output	<code>T *</code>	<code>L4::Ipc::Opt&lt;T&gt; &amp;</code>
<code>L4::Ipc::Opt&lt;Array↔_ref&lt;T&gt; &amp;&gt;</code>	Output	<code>Array_ref&lt;T&gt; &amp;</code>	<code>L4::Ipc::Opt&lt;Array↔_ref&lt;T&gt;&gt; &amp;</code>

### 3.11.2 Server Side Interface

The server side function signature for the Calc example above is

```
long op_sub(Calc::Rights, 14_uint32_t a, 14_uint32_t b, 14_uint32_t &res);
```

The first rights parameter is a bitfield encoding the rights the client has on the used capability in the lower two bits. Currently, the W-right and S-right are supported. The rest of the Rights-bitfield is reserved.

The second and third arguments are input parameters as can be deduced from the tables above. The fourth parameter is an output parameter, delivered to the client with the return value of type long.

### 3.11.3 RPC Return Types

On the server side, the return type of an RPC handling function is always `14_ret_t`. The return value is transmitted via the label field in `14_msgtag_t` and is therefore restricted to its length. Per convention, a negative return value is interpreted as an error condition. If the return value is negative, output parameters are not transmitted back to the client.

**Attention**

The client must never rely on the content of output parameters when the return value is negative.

On the client-side, the return value of the RPC is set as defined in the RPC macro. If `l4_msgtag_t` is given, then the client has access to the full message tag, otherwise the return type should be `l4_ret_t`. Note that the client might not only receive the server return value in response but also an IPC error code.

**3.11.4 RPC Method Declaration**

RPC member functions can be declared using one of the following C++ macros.

For inline RPC stubs, where the RPC stub code itself is `inline`:

- `L4_INLINE_RPC(res, name, (args...), flags)`  
Define an inline RPC call (type and callable).
- `L4_INLINE_RPC_OP(op, res, name, (args...), flags)`  
Define an inline RPC call with specific opcode (type and callable).
- `L4_INLINE_RPC_NF(res, name, (args...), flags)`  
Define an inline RPC call type (the type only, no callable).
- `L4_INLINE_RPC_NF_OP(opcode, Ret_type, func_name, (args...), flags)`  
Define an inline RPC call type with specific opcode (the type only, no callable).

For external RPC stubs, where the RPC stub code must be defined in a separate compile unit (usually a `.cc` file):

- `L4_RPC(Ret_type, func_name, (args...), flags)`  
Define an RPC call (type and callable).
- `L4_RPC_OP(opcode, Ret_type, func_name, (args...), flags)`  
Define an RPC call with specific opcode (type and callable).
- `L4_RPC_NF(Ret_type, func_name, (args...), flags)`  
Define an RPC call type (the type only, no callable).
- `L4_RPC_NF_OP(opcode, Ret_type, func_name, (args...), flags)`  
Define an RPC call type with specific opcode (the type only, no callable).

To generate the implementation of an external RPC stub:

- `L4_RPC_DEF(class_name::func_name)`  
Generate the definition of an RPC stub.

The NF versions of the macro generally do not generate a callable member function named `<name>` but do only generate the type `<name>_t`. This data type can be used to call the RPC stub explicitly using `<name>_t::call(L4::Cap<Iface_class> cap, args...)`.

**3.12 L4Re Build System**

L4Re uses a custom make-based build system, often simply referred to as *BID*.

This section explains how to use BID when writing applications and libraries for L4Re.

### 3.12.1 Building L4Re

#### Setting up the Build Directory

L4Re must be built out-of-source. Therefore the first mandatory step is creating and populating a build directory. From the root of the L4Re source tree run

```
make B=<builddir>
```

Other targets that can be executed in the source directory are

#### update

Update the source directory from svn. Only makes sense when you have downloaded L4Re from the official subversion repository.

#### help

Show a short help with the most important targets.

#### Invoking Make

Once the build directory is set up, BID make can be invoked in one of two ways:

1. Go to the build directory and invoke make without special options.
2. Go to a source directory with a BID make file and invoke `make O=<builddir> . . .`

The default target builds the source (as you would expect), other targets that are available in build mode are

#### cleanfast

Quickly cleans the build directory by removing all subdirectories that contain generated files. The configuration will remain untouched.

#### clean

Remove generated files. Slower than `make cleanfast` but can be used on selected packages. Use `S= . . .` to select the target package.

In addition to these targets, there are a number of targets to generate images which are explained elsewhere.



### 3.12.2 Writing BID Make Files

The BID build system exports different roles that define what should be done in the subdirectory. So a BID make file essentially consists of defining the role and a number of role-dependent make variables. The basic layout should look like this:

```
PKGDIR  ?= <path to package's root directory> # e.g., '.' or '..'
L4DIR   ?= <path to L4Re source directory>    # e.g. '$(PKGDIR)/../..'

<various definitions>

include $(L4DIR)/mk/<role>.mk
```

PKGDIR in the first line defines the root directory of the current package. L4DIR in the next line must be pointed to the root of the [L4Re](#) source tree the package should be built against. After this custom variable definitions for the role follow. In the final line of the file, the make file with the role-specific rules must be sourced.

The following roles are currently defined:

- project.mk - Sub-project Role
- subdir.mk - Directory Role
- [prog.mk - Application Role](#)
- lib.mk - Library Role
- [include.mk - Header File Role](#)
- doc.mk - Documentation Role
- [test.mk - Test Application Role](#)
- idl.mk - IDL File Role (currently unused)
- runux.mk - Tests in FiascoUX Role

#### BID-global Variables

This section lists variables that configure how the BID build system behaves. They are applicable for all roles.

Variable	Description
CC	C compiler for target
CXX	C++ compiler for target
HOST_CC	C compiler for host
HOST_CXX	C++ compiler for host

### 3.12.3 prog.mk - Application Role

The prog role is used to build executable programs.

## General Configuration Variables

The following variables can only be set globally for the Makefile:

MODE

Kind of target to build for. The following values are possible:

- `static` - build a statically linked binary (default)
- `shared` - build a dynamically linked binary
- `l4linux` - build a binary for running on L4Linux on the target platform
- `host` - build for host system
- `targetsys` - build a binary for the target platform with the compiler's default settings

SYSTEMS

List of architectures the target can be built for. The entries must be space-separated entries either naming an architecture (e.g. `amd64`) or an architecture and ABI (e.g. `arm-l4f`). When not defined, the target will be built for all possible platforms.

TARGET

Name or names of the binaries to compile. This variable may also be postfixed with a specific architecture.

## Target-specific Configuration Variables

The following variables may either be used with or without a description suffix. Without suffix they will be used for all operations. With a specific description their use is restricted to a subset. These specifications include a target file and the architecture, both optional but in this order, separated by underscores. The specific variables will be used in addition to the more general ones.

`SRC_C / SRC_CC / SRC_F / SRC_S`

`.c, .cc, .f90, .S` source files.

`REQUIRES_LIBS`

List of libraries the binary depends on. This works only with libraries that export a `pkg_config` configuration file. Automatically adds any required include and link options.

DEPENDS\_PKGS

List of packages this binary depends on. If one these packages is missing then building of the binary will be skipped.

CPPFLAGS / CFLAGS / CXXFLAGS / FFLAGS / ASFLAGS

Options for the C preprocessor, C compiler, C++ compiler, Fortran compiler and assembler. When used with suffix, the referred element is the source file, not the target file.

LDFLAGS

Options for the linker ld.

LIBS

Additional libraries to link against (with -l).

PRIVATE\_LIBDIR

Additional directories to search for libraries.

CRT0 / CRTN

(expert use only) Files containing custom startup and finish code.

LDSCRIPT

(expert use only) Custom link script to use.

### 3.12.4 include.mk - Header File Role

The header file role is responsible for installing header file at the appropriate location.

The following variables can be used for customizing the process:

`INCSRC_DIR`

Source directory where the headers can be found. Default is the directory where the Makefile resides.

`TARGET`

List of header files to install. If left undefined, then `INCSRC_DIR` will be scanned for files with suffix `.h` or `.i`.

Supports the specification of special filenames to allow for different source and target filenames to be installed. The syntax is `TARGET<SRC`, where a filename including the path of `SRC` is installed as `TARGET`. An example is

```
libfoo.h<contrib/libfoo_linux.h
```

which installs the header from the `contrib` directory under the name without that `contrib` directory and without the platform specific suffix.

`EXTRA_TARGET`

When `TARGET` is undefined, then add these files to the headers found by scanning the source directory. Has no effect if `TARGET` has been defined.

The filenames specified allow for the same rule specifications as supported by `TARGET`.

`CONTRIB_HEADERS`

When set, the headers will be installed in `${BUILDDIR}/include/contrib/${PKGNAME}` rather than `${BUILDDIR}/include/l4/${PKGNAME}`.

`INSTALL_INC_PREFIX`

Base directory where to install the headers. Overwrites `CONTRIB_HEADERS`. The headers will then be found under `${BUILDDIR}/include/${INSTALL_INC_PREFIX}`.

`PC_FILENAME`

When set, a `pkg_config` configuration file is created with the given name.

### 3.12.5 test.mk - Test Application Role

The test role is very similar to the application role, it also builds an executable binary.

The difference is that it also builds for each target a test script that executes the test target either on the host (MODE=host) or a target platform (currently only qemu).

The role accepts all make variables that are accepted by the application role. The only difference is that the `TARGET` variable is not required. If it is missing, the source directory will be scanned for source files that fit the pattern `test_*.c[c]` and create one target for each of them.

#### Note

It is possible to still use `SRC_C[C]` when targets are determined automatically. In that case the specified sources will be used in addition\* to the main `test_*.c[c]` source.

In addition to the variables above, there are a number of variables that control how the test is executed. All these variables may be used as a global variable that applies to all test or, if the target name is added as a suffix, set for a specific target only.

#### TEST\_TARGET

Name of binary containing the test (default: same as `TARGET`).

#### TARGET\_\$ (ARCH)

When `TARGET` is undefined, these targets are added to the list of targets for the specified architecture. For all targets `SRC_C[C]` files must be defined separately.

#### TEST\_KERNEL\_ARGS

Arguments to append to the kernel command line. These are also appended when specifying custom ones via a `.t`-file's `-f` parameter or when using `-d`.

#### TEST\_EXPECTED

File containing expected output. By default the variable is empty, which means the test binary is expected to produce TAP test output, that can be directly processed. When the `TEST_TAP_PLUGINS` variable is given, `TEST_EXPECTED` is ignored.

#### TEST\_EXPECTED\_REPEAT

Number of times the expected output should be repeated, by default 1. When set to 0 then output is expected to repeat forever. This is particularly useful to make sure that stress tests that are meant to run in an endless loop are still alive. Note that such endless tests can only be run by directly executing the test script. They will be skipped when run in a test harness like `prove`.

`TEST_TAP_PLUGINS`

Specify the plugins that are used to process the output of the test run. The syntax is of the values is:

`plugin1:arg1=a,arg2=b plugin2:arg=foo`

Multiple plugins separated by a space are loaded in order. Spaces are not allowed inside a plugin specification. One or more arguments are optionally passed to the plugin separated by commas and delimited by a colon.

If the variable is not specified the plugins for `TAPOutput` and `OutputMatching` (depending on the `TEST_EXPECTED` variable) are automatically loaded.

For the supported plugins and their options please refer to their in-line documentation in `tool/lib/L4/TapWrapper/Plugin/`. The plugin name corresponds to the file stem name in that directory.

`TEST_TIMEOUT`

Non-standard timeout after which the test run is aborted (useful for tests involving sleep).

`NED_CFG`

LUA configuration file for startup to give to Ned

`REQUIRED_MODULES`

Additional modules needed to run the test. By adding `[opts]` to the name of a module you can add module options that are reflected in the generated `modules.list`.

`BOOTSTRAP_ARGS`

Additional parameters to supply to bootstrap.

`QEMU_ARGS`

Additional parameters to supply to QEMU.

`MOE_ARGS`

Additional parameters to supply to moe.

`TEST_ARGS`

Additional arguments for the `TEST_STARTER` (tapper-wrapper per default).

`TEST_ROOT_TASK`

Alternative root task to be used during a test instead of moe.

`TEST_ROOT_TASK_ARGS`

Arguments passed to `TEST_ROOT_TASK` if `TEST_ROOT_TASK` is different from moe.

`KERNEL_CONF`

Features the [L4Re](#) Microkernel must have been compiled with. A space-separated list of config options as used by Kconfig. `run_test` looks for a `globalconfig.out` file in the same directory as the kernel and checks that all options are enabled. If not, the test is skipped. Has only an effect if the `globalconfig.out` file is present.

`L4RE_CONF`

Features the [L4Re](#) userland must have been compiled with. A space-separated list of config options as used by Kconfig. `run_test` will look for these in the `.kconfig` file in the [L4Re](#) build directory.

`L4LINUX_CONF`

Features the L4Linux kernel must have been compiled with. Similar to `KERNEL_CONF` but checks for a `.config` file in the directory of the L4Linux kernel.

`TEST_SETUP`

Command to execute before the test is run. The test will only be executed if the command returns 0. If the exit code is 69, the test is marked as skipped with the reason provided in the final line of stdout.

`TEST_LOGFILE`

Append output of test execution to the given file unless `TEST_WORKDIR` is given.

`TEST_WORKDIR`

Create logs, temp and other files below the given directory. That directory is taken as base dir for more automatically created subdir levels using the current test path, in order to guarantee conflict-free usage when running many different tests with a common workdir. When `TEST_WORKDIR` is provided then `TEST_LOGFILE` is ignored as it is organized below workdir.

`TEST_TAGS`

List of conditions for tags provided during execution of a test. A tag can be set to 1, set to 0 or be unspecified via `TEST_RUN_TAGS` during execution. Therefore there are 4 possible conditions for a tag that can be specified in `TEST_TAGS`: `tag`, `!tag`, `+tag` and `-tag`. The following table shows the conditions they represent.

<code>TEST_RUN_TAGS \ TEST_TAGS</code>	<code>tag</code>	<code>!tag</code>	<code>+tag</code>	<code>-tag</code>
<code>tag</code> or <code>tag=1</code>	y		y	
unspecified		y	y	
<code>tag=0</code>		y		y

*Example usage:*

The tag `long-running` is used by tests which take a long time and should be skipped by default. These tests are marked with the tag `long-running` unprefixd.

The tag `hardware` is set to 1 at runtime when the tests will run on real hardware. Tests that must not run on real hardware are marked with `!hardware`.

The tag `+impl-def` is used by tests that test implementation details. Due to the nature of this flag we require the "+" prefix to be used, so they are run by default but can be excluded from execution by setting `TEST_RUN_TAGS` to `impl-def=0` at runtime.

If you want to specify multiple tag conditions they need to be separated with a comma.

**TEST\_PLATFORM\_ALLOW and TEST\_PLATFORM\_DENY**

Deny and allow lists of platforms a test is banned from or limited to. If you list platforms in the TEST\_PLATFORM\_ALLOW variable the test will only be run on these listed platforms and will be skipped on any other platform. If you list platforms in the TEST\_PLATFORM\_DENY variable the test will be skipped on the listed platforms and will be run on any other platform. You can only use one of these variables per test, not both. See mk/platforms/ for the various identifiers.

*Example usage:*

```
# Do not run this test on the Raspberry Pi platform
TEST_PLATFORM_DENY_test_xyz := rpi

# Only run this test on this test on the RCar3 platform.
TEST_PLATFORM_ALLOW_test_abc := rcar3
```

**TAPARCHIVE**

Filename for an archive file to store the resulting TAP output.

In addition to compiled tests, it is also possible to create tests where the test binary or script comes from a different source. These tests must be listed in EXTRA\_TARGET and for each target a custom TEST\_TARGET must be provided.

**Running Tests**

The make role creates a test script which can be found in <builddir>/test/t/<arch>/<api>. It is possible to organise the tests further in subdirectories below by specifying a TEST\_GROUP.

To be able to execute the test, a minimal test environment needs to be set up by exporting the following environment variables:

KERNEL\_<arch>, KERNEL

**L4Re** Microkernel binary to use. The test runner is able to check if the kernel has all features necessary for the test and skip tests accordingly. In order for this to work, the globalconfig.out config file from the build directory needs to be available in the same directory as the kernel.

L4LX\_KERNEL\_<arch>, L4LX\_KERNEL

L4Linux binary to use. This is only required to run tests in mode=l4linux. If no L4Linux kernel is set then these tests will simply be skipped. The test runner is also able to check if the kernel has all features compiled in that are required to run the test successfully (see make variable L4LINUX\_CONF above). For this to work, the .config configuration file from the build directory needs to be available in the same directory as the kernel.

LINUX\_RAMDISK\_<arch>, LINUX\_RAMDISK

Ramdisk to mount as root in L4Linux. This is only required to run tests in mode=l4linux. If not supplied, L4Linux tests will be skipped. The ramdisk must be set up to start the test directly after the initial startup is finished. The name of the test binary is supplied via the kernel command line option l4re\_testprog. The tool/test directory contains an example script launch-l4linux-test. which can be copied onto the ramdisk and started by the init script.



## TEST\_HWCONFIG and TEST\_FIASCOCONFIG

Some userland tests rely on external information about the underlying platform and the configuration of the [L4Re](#) Microkernel to decide whether or not to test specific features or to determine which and how much resources are available. Some examples for this are whether or not virtualization is supported by the platform, how many cores the platform has, how many cores the kernel supports or how much memory the platform provides. To convey this information to these tests you can set the two environment variables `TEST_HWCONFIG` and `TEST_FIASCOCONFIG`.

Using `TEST_HWCONFIG` requires a plain text document containing key-value pairs separated by a `=` symbol. On top of that comment lines starting with `#` are supported. Simply create a plain text file such as the following and set `TEST_HWCONFIG` to its absolute path.

```
VIRTUALIZATION=y
MP=y
NUM_CORES=4
MEMORY=2048
```

Using `TEST_FIASCOCONFIG` is easier since it only needs to contain the absolute path of the `globalconfig.out` file in the [L4Re](#) Microkernel's build directory. The build system will then extract the information when a test is started.

When starting a test the build system will read both files and provide their content as a lua table to the test. A lua script can then make decisions based on them. To simplify some decisions the build system merges some information by itself, e.g. virtualization is only available if both the platform and the [L4Re](#) Microkernel support this feature. More details can be obtained from the perl module in `tool/lib/L4/TestEnvLua.pm`.

In addition to these variables, the following BID variables can be overwritten at runtime: `PT` (for the platform type) and `TEST_TIMEOUT`. You may also supply `QEMU_ARGS` and `MOE_ARGS` which will be appended to the parameters specified in the BID test make file.

Once the environment is set up, the tests can be run either by simply executing all of them from the build directory with

```
make test
```

or executing them directly, like

```
test/t/amd64_amdfam10/14f/14re-core/moe/test_namespace.t
```

or running one or more tests through the test harness `prove`, like

```
prove test/t/amd64_amdfam10/14f/14re-core/moe/test_namespace.t
prove -r test/t/amd64_amdfam10/14f/14re-core/
prove -rv test/t/amd64_amdfam10/14f/14re-core/
```

`TEST_TAGS` allow for a way to include or exclude whole groups of tests during execution, primarily with `prove`. You can specify which tests to run at runtime using one of the following ways:

```
$ test/t/amd64_amdfam10/14f/14re-core/test_one.t --run-tags slow,gtest-shuffle=0
$ test/t/amd64_amdfam10/14f/14re-core/test_one.t -T slow,gtest-shuffle=0
$ prove -r test/t/amd64_amdfam10/14f/14re-core/ : -T slow,gtest-shuffle=0
$ TEST_RUN_TAGS=slow,gtest-shuffle=0 prove -r test/t/amd64_amdfam10/14f/14re-core/
```

For each test tag requirements defined in the corresponding `TEST_TAGS` Makefile variable are tested. If the requirements for tags do not match the test is skipped. The `SKIP` message will provide insight why the test was skipped:

```
$ make test
...
test/t/amd64_amdfam10/test_one.t .... ok
test/t/amd64_amdfam10/test_two.t .... skipped: Running this test requires tag slow to be set to 1.
test/t/amd64_amdfam10/test_three.t .. ok
```

When tags are provided, the tests requiring those tags are now also executed while the tests that forbid them are skipped:

```
$ TEST_RUN_TAGS=slow,gtest-shuffle
$ make test
...
test/t/amd64_amdfam10/test_one.t .... ok
test/t/amd64_amdfam10/test_two.t .... ok
test/t/amd64_amdfam10/test_three.t .. skipped: Running this test requires tag gtest-shuffle to be set to 0 or
```

For further details on how values in `TEST_TAGS` and `TEST_RUN_TAGS` interact, see the help text for `TEST_TAGS`.

## Running Tests in External Programs

You can hand-over test execution to an external program by setting the environment variable `EXTERNAL_TEST_STARTER` to the full path of that program:

```
export EXTERNAL_TEST_STARTER=/path/to/external/test-starter
make test
```

`EXTERNAL_TEST_STARTER`

This variable is evaluated by `tool/bin/run_test` (the backend behind `make test`) and contains the full path to the tool which actually starts the test instead of the test itself.

The `EXTERNAL_TEST_STARTER` can be any program instead of the default execution via `make qemu E=make test`. Its output is taken by `run_test` as the test output.

Usually it is just a bridge to prepare the test execution, e.g., it could create the test as image and start that image via a simulator.

## Running Tests in a Simulator

Based on above mechanism there is a dedicated external test starter `tool/bin/teststarter-image-telnet.pl` shipped in BID which assumes an image to be started with another program which provides test execution output on a network port.

This can be used to execute tests in a simulator, like this:

```
export EXTERNAL_TEST_STARTER=$L4RE_SRC/tool/bin/teststarter-image-telnet.pl
export SIMULATOR_START=/path/to/configured/simulator-exe
make test
```

After building the image and starting the simulator it contacts the simulator via a network port (sometimes called "telnet" port) to pass-through its execution output as its own output so it gets captured by `run_test` as usual.

The following variables control `teststarter-image-telnet.pl`:

#### SIMULATOR\_START

This points to the full path of the program that actually starts the prepared test image. Most often this is the frontend script of your simulator environment which is pre-configured so that it actually works in the way that `teststarter-image-telnet.pl` expects from the following settings.

#### SIMULATOR\_IMAGETYPE

The image type to be generated via `make $SIMULATOR_IMAGETYPE E=maketest`. Default is `elfimage`.

#### SIMULATOR\_HOST

The simulator will be contacted via socket on that host to read its output. Default is `localhost`.

#### SIMULATOR\_PORT

The simulator will be contacted via socket on that port to read its output. Default is `11111`.

#### SIMULATOR\_START\_SLEEPTIME

After starting the simulator it waits that many seconds before reading from the port. Default is `1` (second).

### Running tests without tapper-wrapper

In case you want to replace the `tapper-wrapper` test starter, you can replace the default one by setting the environment variable `TEST_STARTER` to the path of your test starter. Then your test starter can use the same environment which is normally set up for the default starter, which includes environment variables provided by the build system as well as the test itself. Among these are `SEARCHPATH`, `MODE`, `ARCH`, `MOE_CFG`, `MOE_ARGS`, `TEST_TIMEOUT`, `TEST_TARGET`, `TEST_EXPECTED`, `QEMU_ARGS` and many more.

### Debugging Tests

The test script is only a thin wrapper that sets up the test environment as it was defined in the make file and then executes two scripts: `tapper-wrapper` and `run_test`.

The main work horse of the two is `tool/bin/run_test`. It collects the necessary files and starts `qemu` to execute the test. This script is always required.

There is then a second script wrapped around the test runner: `tool/bin/tapper-wrapper`. This tool inspects the output of the test runner and reformats it, so that it can be read by tools like `prove`. If the test produces tap output, then the script scans for this output and filters away all the debug output. If `TEST_EXPECTED` was defined, then the script scans the output for the expected lines and prints a suitable TAP message with success or failure. It also makes sure that `qemu` is killed as soon as the test is finished.

There are a number of command-line parameters that allow to quickly change test parameters for debugging purposes. Run the test with `'-help'` for more information about available parameters.

### 3.13 Kernel Factory

The kernel factory is a kernel object that provides the ability to create new kernel objects dynamically.

The kernel factory enforces a memory quota. This quota defines the maximum amount of kernel memory the factory service can use to construct the requested objects. When the quota is depleted, the factory refuses the creation of new objects.

The quota may be higher than the amount of available kernel memory; ultimately, the amount of available kernel memory is the strict limit for the factory to remain operational.

The kernel factory creates the following kinds of objects:

- [DMA space](#)
- [L4::Factory](#)
- [L4::lpc\\_gate](#) ([L4\\_PROTO\\_NONE](#), [L4\\_PROTO\\_KOBJECT](#))
- [L4::Irq](#) ([L4\\_PROTO\\_IRQ\\_SENDER](#))
- [L4::Semaphore](#)
- [L4::Task](#)
- [L4::Thread](#)
- [L4::Vm](#)
- [L4::Vcpu\\_context](#)

The protocol IDs for objects in this list are given in [L4\\_msgtag\\_protocol](#). Kernel objects whose protocol ID is not immediately clear from the documentation of [L4\\_msgtag\\_protocol](#) have their protocol IDs stated within parenthesis. As an exception, [L4::lpc\\_gate](#) can be identified by more than one protocol IDs. The protocol ID shall be used as the second argument for [L4::Factory.create](#)([Cap<void>](#), long, [l4\\_utcb\\_t \\*](#)).

For the C++ interface see [L4::Factory](#), for the C interface see [Factory](#).

#### 3.13.1 Passing parameters for the create stream

[L4::Factory.create\(\)](#) returns a [create stream](#) that allows arguments to be forwarded to the constructor of the object to be created.

Objects that support additional parameters on their creation are presented with a non-empty list of parameters. The parameters are listed in the order they should be provided to a create stream returned by [L4::Factory.create\(\)](#).

- [Dmar\\_space\(\)](#)
- [L4::Factory\(l4\\_umword\\_t\)](#)
  - Argument: factory quota (in bytes).
  - See [L4::Factory.create\\_factory\(\)](#) for details.
- [L4::lpc\\_gate\(\)](#)
  - Creates an unbound IPC gate.
  - Alternatively, an IPC gate can be immediately bound to a thread upon creation using [L4::Factory.create\\_gate\(\)](#).

- [L4::Irq\(\)](#)
- [L4::Semaphore\(\)](#)
- [L4::Task\(l4\\_fpage\\_t\)](#)
  - Argument: utcb\_area
  - See [L4::Factory.create\\_task\(\)](#) for details.
- [L4::Thread\(\)](#)
- [L4::Vm\(\)](#)
- [L4::Vcpu\\_context\(\)](#)



# Chapter 4

## L4Re Servers

Here you shall find a quick overview over the standard services running on the [L4Re](#) Microkernel.

### Sigma0, the Root Pager

Sigma0 is a special server running on [L4](#) because it is responsible of resolving page faults for the root task, the first useful task on [L4Re](#). Sigma0 can be seen as part of the kernel, however it runs in unprivileged mode. To run something useful on the [L4Re](#) Microkernel you usually need to run Sigma0, nevertheless it is possible to replace Sigma0 by a different implementation.

For more details see [Sigma0, the Root-Pager](#)

### Moe, the Root Task

Moe is our implementation of the [L4](#) root task that is responsible for bootstrapping the system, and to provide basic resource management services to the applications on top. Therefore Moe provides [L4Re](#) resource management and multiplexing services:

- **Memory** in the form of memory allocators ([L4Re::Mem\\_alloc](#), [L4::Factory](#)) and data spaces ([L4Re::Dataspace](#))
- **Cpu** in the form of basic scheduler objects ([L4::Scheduler](#))
- **Vcon** multiplexing for debug output (output only)
- **Virtual memory management** for applications, [L4Re::Rm](#)

Moe further provides an implementation of [L4Re](#) name spaces ([L4Re::Namespace](#)), which are for example used to provide a read only directory of all multi-boot modules. In the case of a boot loader, like grub that enables a VESA frame buffer, there is also a single instance of an [L4Re](#) graphics session ([L4Re::Goos](#)).

To start the system Moe starts a single ELF program, the init process. The init process (usually Ned, see the next section) gets access to all resources managed by Moe and to the Sigma0 root pager interface.

For more details see [Moe, the Root-Task](#).

## Ned, the Default Init Process

To keep the root task free from complicated scripting engines and to avoid circular dependencies in application startup (that could lead to dead locks) the configuration and startup of the real system is managed by an extra task, the init process.

Ned is such an init process that allows system configuration via Lua scripts.

For more information see [Ned](#).

## Io, the Platform and Device Resource Manager

Because all peripheral management in [L4Re](#) is done in user-level applications, there is the need to have a centralized management of the resources belonging to the platform and to peripheral devices.

This is the job of Io. Io provides portable abstractions for iterating and accessing devices and their resources (IRQ's, IO Memory...), as well as delegating access to those resources to other applications (e.g., device drivers).

For more details see [Io, the Io Server](#).

## Other Servers

The following additional server package are available on top of the core [L4Re](#) environment.

- [Rtc, the Real-Time Clock Server](#)  
is a simple multiplexer for real-time clock hardware on your platform.
- [fb-drv, the Low-Level Graphics Driver](#)  
provides low-level access and initialization of various graphics hardware. It has support for running VESA BIOS calls on Intel x86 platforms, as well as support for various ARM display controllers. `fb-drv` provides a single instance of the `L4Re::Goos` interface and can serve as a back end for the Mag server, in particular, if there is no graphics support in the boot loader.
- [Virtio Net P2P, a virtual network point-to-point link](#)
- [Virtio Net Switch, a virtual network switch](#)
- [Uvmm, the virtual machine monitor](#)
- [RTC driver](#)
- [Mag, the GUI Multiplexer](#)
- [Sigma0, the Root-Pager](#)
- [Cons, the Console Multiplexer](#)

### 4.1 Sigma0, the Root-Pager

Sigma0 is a special [L4](#) server that serves as the origin for mapping memory.

It is started by Fiasco.OC on the system boot and gets full access to all userland RAM and device memory. It functions as the pager (main memory provider) for Moe and as the provider for device memory for Io. Moe and Io are trusted and usually the only applications besides Ned that get a capability for Sigma0. Memory can be requested from Sigma0 directly via an IPC, or indirectly by causing page faults and having them resolved by Sigma0.



### 4.1.1 Factory

There is only one instance of Sigma0 in an [L4Re](#) system, which is made accessible to Moe via an IPC gate capability. Using this capability, Moe can request Sigma0 to create new communication channels to itself by creating additional IPC gate capabilities. This request is done using the [L4::Factory](#) interface. This is the only kind of object that can be created by the factory in Sigma0.

List of objects that the Sigma0 Factory can create:

- Sigma0 ()
  - Use protocol id [L4\\_PROTO\\_SIGMA0](#) for creation
  - No arguments supported

See also

[Sigma0 API](#)

## 4.2 Moe

Moe is the default root-task implementation for L4Re-based systems.

*Moe* is the first task which is usually started in L4Re-based systems. The microkernel starts *Moe* as the Root-Task.

### 4.2.1 Moe objects

Moe provides a default implementation for the basic [L4Re](#) abstractions, such as data spaces ([L4Re::Dataspace](#)), region maps ([L4Re::Rm](#)), memory allocators ([L4::Factory](#), [L4Re::Mem\\_alloc](#)), name spaces ([L4Re::Namespace](#)) and so on (see [L4Re Interface](#)). These are described in the following subsections.

#### 4.2.1.1 Factory

The factory in Moe is responsible for all kinds of dynamic object allocation.

Moe's factory allows allocation of the following objects:

- [L4Re::Namespace](#)
- [L4Re::Dataspace](#), RAM allocation
- [L4Re::Dma\\_space](#), memory management for DMA-capable devices
- [L4Re::Rm](#), virtual memory management for application tasks
- [L4::Vcon](#) (output only)
- [L4::Scheduler](#), to provide a restricted priority / CPU range for clients
- [L4::Factory](#), to provide a quota limited allocation for clients

Note

[L4::Scheduler](#) objects can be only created through the user factory provided by Moe to the initial application. Other factory instances cannot create this object.

#### 4.2.1.1.1 Passing parameters to the create stream

`L4::Factory.create()` returns a [create stream](#) that allows arguments to be forwarded to the object creation in Moe.

### Namespace

Moe provides a name space conforming to the [L4Re::Namespace](#) interface (see [Namespace](#)). Per default Moe creates a single name space for the [Boot FS](#). That is available as `rom` in the initial objects of the init process.

#### 4.2.1.1.2 Boot FS

The Boot FS subsystem provides access to the files loaded during the platform boot (or available in ROM). These files are either linked into the boot image or loaded via a flexible boot loader, such as GRUB.

The subsystem provides an [L4Re::Namespace](#) object as directory and an [L4Re::Dataspace](#) object for each file.

By default all files are read only and visible in the namespace `rom`. As an option, files can be supplied with the argument `:rw` to mark them as writable modules. Moe will allow read and write access to these dataspace and make them visible in a different namespace called `rwfs`.

An example entry in 'modules.list' would look like this:

```
module somemodule :rw
```

### Note

In order for a client to receive write permissions to the dataspace, the corresponding cap also needs write permissions.

### Capabilities

- `svr`  
Server Capability of application. Endpoint for IPC calls  
Mandatory capability.

### Command Line Options

- `--debug=<flags>`  
This option enables debug messages from Moe itself.  
Multiple Flags in one string separated through '|', '+' or ','.  
Possible values for `<flags>` are
  - info
  - warn
  - boot
  - server
  - exceptions
  - loader
  - ns

- all
- `--init=<init_process>`

This options allows to set the init process binary.

String value.

Default: `rom/ned`
- `--l4re-dbg=<flags>`

This option allows to set the debug options for the [L4Re](#) runtime environment of the init process.

Multiple Flags in one string separated through '|', '+' or ','.

Possible values for `<flags>` are

  - info
  - warn
  - boot
  - server
  - exceptions
  - loader
  - ns
  - all
- `--ldr-flags=<flags>`

This option allows setting some loader options for the [L4Re](#) runtime environment.

Multiple Flags in one string separated through '|', '+' or ','.

Possible values for `<flags>` are

  - pre\_alloc
  - all\_segs\_cow
  - pinned\_segs
- `--brk=<address>`

This option is only present on systems without MMU. It restricts dynamic allocations to addresses equal or higher than `<address>`. Use it to prevent moe from allocating memory in regions that shall later be used by other applications or virtual machines.

Hexadecimal number without '0x' prefix.
- `-- <init_options>`

All command-line parameters after the special `--` option are passed directly to the init process.

## Namespace

Call: `create (L4.Proto.Namespace)`

## Dataspace

Dataspaces can be allocated with an arbitrary size. The granularity for memory allocation however is the machine page size ([L4\\_PAGESIZE](#)). A dataspace user must be aware that, as a result of this page-size granularity, there may be padding memory at the end of a dataspace which is accessible to each client. Moe currently allows most dataspace operations on this padding area. Nonetheless, the client must not make any assumptions about the size or content of the padding area, as this behaviour might change in the future.

The provided data spaces can have different characteristics:

- Physically contiguous and pre-allocated
- Non contiguous and on-demand allocated with possible copy on write (COW)

Dataspaces allocated via the Moe's factory allow mappings with any combination of the read-write-execute (RWX) rights, subject to a possible restriction of the writable right for client capabilities lacking the 'W' right.

Call: `create(L4.Proto.Dataspace, size [, flags, align])`

- `size`  
Size in bytes.  
Numerical value.
- `flags`  
Special dataspace properties  
Bitmap of length 4 with the single bits holding the following meaning:
  - 0x01: Continuous Allocate physically contiguous memory.
  - 0x02: Pinned Deprecated, use [L4Re::Dma\\_space](#) instead.
  - 0x04: Super pages Allocate super pages.
  - 0x08: Fixed physical Address Allocate at fixed physical address. Only honored on no-MMU systems. Will fail on MMU systems.
- `align`  
Log2 alignment of dataspace if supported by allocator  
Numerical value.

## DMA space

Call: `create(L4.Proto.Dma_space)`

## Region Map

Call: `create(L4.Proto.Rm)`

## Virtual console

The logging facility of Moe provides per application tagged and synchronized log output.

Call: `create(L4.Proto.Log [, label, "color=(string|int)"])`

- `label`

Label used as prefix for the console output.

String value.

- `"color=(string|int) "`

Color of client's output

The Value for this parameter can be one of the following:

- `string`

Define the color by the first character of the given string

Possible values are

- \* `n`: gray
- \* `r`: red
- \* `g`: green
- \* `y`: yellow
- \* `b`: blue
- \* `m`: magenta
- \* `c`: cyan
- \* `w`: white
- \* `N`: black
- \* `R`: light red
- \* `G`: light green
- \* `Y`: light yellow
- \* `B`: light blue
- \* `M`: light magenta
- \* `C`: light cyan
- \* `W`: bright white

- `int`

Define the color by integer.

Possible values are

- \* `0`: gray
- \* `1`: red
- \* `2`: green
- \* `3`: yellow
- \* `4`: blue
- \* `5`: magenta
- \* `6`: cyan
- \* `7`: white
- \* `8`: black
- \* `9`: light red
- \* `10`: light green
- \* `11`: light yellow
- \* `12`: light blue
- \* `13`: light magenta
- \* `14`: light cyan
- \* `15`: bright white

Default: `white`

## Scheduler

The scheduler subsystem provides a simple scheduler proxy for scheduling policy enforcement.

The priority offset provided on the creation of a scheduler proxy defines the minimum priority assigned to threads which are scheduled by that instance of the scheduler proxy. The offset is implicitly added to priorities provided to `L4::Scheduler.run_thread()`.

Call: `create(L4.Proto.Scheduler, limit, offset [, bitmap])`

- `limit`  
Maximum priority.  
Numerical value.
- `offset`  
Priority offset.  
Numerical value.
- `bitmap`  
Bitmap of CPUs - can be repeated to address higher order CPUs  
Numerical value.

## Factory

Call: `create(L4.Proto.Factory [, quota])`

- `quota`  
Limit in bytes. The limit is deducted from the limit of the factory that creates the new factory.  
Numerical value.
  - Must not be zero.

## 4.3 Ned, the Init Process

Ned's job is to bootstrap the system running on [L4Re](#).

The main thing to do here is to coordinate the startup of services and applications as well as to provide the communication channels for them. The central facility in Ned is the Lua (<http://www.lua.org>) script interpreter with the [L4Re](#) and ELF-loader bindings.

The boot process is based on the execution of one or more Lua scripts that create communication channels (IPC gates), instantiate other [L4Re](#) objects, organize capabilities to these objects in sets, and start application processes with access to those objects (or based on those objects).

For starting applications, Ned depends on the services of [Moe](#) or another *loader*, which must provide data spaces and region maps. Ned also uses the 'rom' capability as source for Lua scripts and at least the 'l4re' binary (the runtime environment core) running in each application.

Each application Ned starts is equipped with an [L4Re::Env](#) environment that provides information about all the initial objects made accessible to this application.

### 4.3.1 Lua Bindings for L4Re

Ned provides various bindings for [L4Re](#) abstractions. These bindings are located in the 'L4' package (`require "L4"`).

#### 4.3.1.1 Tutorial

For a verbose example using the Ned Lua bindings, see [tutorial.lua](#).

#### 4.3.1.2 Capabilities in Lua

Capabilities are handled as normal values in Lua. They can be stored in normal variables or Lua compound structures (tables). A capability in Lua possesses additional information about the access rights that shall be transferred to other tasks when the capability is transferred. To support implementation of the Principle of Least Privilege, minimal rights are assigned by default. Extended rights can be added using the method `mode("...")` (short `m("...")`) that returns a new reference to the capability with the given rights.

#### Note

It is generally impossible to elevate the real access rights to an object. This means that if Ned has only restricted rights to an object it is not possible to upgrade the access rights with the `mode` method.

The capabilities in Lua also carry dynamic type information about the referenced objects. They thereby provide type-specific operations on the objects, such as the `create` operation on a generic factory or the `query` and `register` operations on a name space.

#### 4.3.1.3 Access to L4Re::Env Capabilities

The initial objects provided to Ned itself are accessible via the table `L4.Env`. The default (usually unnamed) capabilities are accessible as `factory`, `log`, `mem_alloc`, `parent`, `rm`, and `scheduler` in the `L4.Env` table.

#### 4.3.1.4 Constants

#### Protocols

The protocol constants are defined by default in the [L4](#) package's table `L4.Proto`. The definition is not complete and only covers what is usually needed to configure and start applications. The protocols are for example used as first argument to the `Factory:create` method.

```
Proto = {
  Dataspace = 0x4000,
  Namespace = 0x4001,
  Goos      = 0x4003,
  Mem_alloc = 0x4004,
  Rm        = 0x4005,
  Event     = 0x4006,
  Inhibitor = 0x4007,
  Sigma0    = -6,
  Log       = -13,
  Scheduler = -14,
  Factory   = -15,
  Vm        = -16,
  Dma_space = -17,
  Irq_sender = -18,
  Semaphore = -20,
```

```

Iommu      = -22,
Ipc_gate   = 0,
}

```

## Rights

The rights of a Lua capability can be defined in two ways via the `:mode()` interface. Either via a string representation of the rights or via an integer value. An example for the former is `:mode("rsnc")` while the latter equivalent is `:mode(L4.Rights.r | L4.Rights.s | L4.Rights.n | L4.Rights.c)`. The following listing shows the integer constants. The constant names can be used in the string parameter to `:mode()`.

```

Rights = {
  s = 2,
  w = 1,
  r = 4,
  d = 8,
  n = 16,
  c = 32,
  ro = 4,
  rw = 5,
  rws = 7,
}

```

## Debugging Flags

Debugging flags used for the applications [L4Re](#) core:

```

Dbg = {
  Info      = 1,
  Warn      = 2,
  Boot      = 4,
  Server     = 0x10,
  Exceptions = 0x20,
  Cmd_line  = 0x40,
  Loader     = 0x80,
  Name_space = 0x400,
  All       = 0xffffffff,
}

```

## Loader Flags

Flags for configuring the loading process of an application.

```

Ldr_flags = {
  eager_map    = 0x1, -- L4RE_AUX_LDR_FLAG_EAGER_MAP
  all_segs_cow = 0x2, -- L4RE_AUX_LDR_FLAG_ALL_SEGS_COW
  pinned_segs  = 0x4, -- L4RE_AUX_LDR_FLAG_PINNED_SEGS
}

```

### 4.3.1.5 Application Startup Details

The central facility for starting a new task with Ned is the class `L4.Loader`. This class provides interfaces for conveniently configuring and starting programs. It provides three operations:

- `new_channel()` Returns a new IPC gate that can be used to connect two applications
- `start()` and `startv()` Start a new application process and return a process object

The `new_channel()` call is used to provide a service application with a communication channel to bind its initial service to. The concrete behavior of the object and the number of IPC gates required by a server depends on the server implementation. The channel can be passed to client applications as well or can be used for operations within the script itself.

`start()` and `startv()` always require at least two arguments. The first one is a table that contains information about the initial objects an application shall get. The second argument is a string, which for `start()` is the program name plus a white-space-separated list of program arguments (`argv`). For `startv()` the second argument is just the program binary name – which may contain spaces –, and the program arguments are provided as separate string arguments following the binary name (allowing spaces in arguments, too). The last optional argument is a table containing the POSIX environment variables for the program.

The Loader class uses reasonable defaults for most of the initial objects. However, you can override any initial object with some user-defined values. The main elements of the initial object table are:



- `factory` The factory used by the new process to create new kernel objects, such as threads etc. This must be a capability to an object implementing the [L4Re::Factory](#) protocol and defaults to the factory object provided to Ned.
- `mem` The memory allocator provided to the application and used by Ned allocates data spaces for the process. This defaults to Ned's memory allocator object (see [L4Re::Mem\\_alloc](#)).
- `rm_fab` The generic factory object used to allocate the region-map object for the process. (defaults to Ned's memory allocator).
- `log_fab` The generic factory to create the [L4Re::Log](#) object for the application's output (defaults to Ned's memory allocator). The `create` method of the `log_fab` object is called with `log_tag` and `log_color`, from this table, as arguments.
- `log` A table with parameters passed to the `log_fab`:
  - The first item is a short string defining the tag used for tagging log output of this process (defaults to the program name).
  - The second item is a string defining the color used for the log tag and the log string (defaults to "white").
  - Further parameters might be evaluated by certain implementations of the [L4Re::Log](#) interface.
- `scheduler` The scheduler object used for the process' threads (defaults to Ned's own scheduler).
- `caps` The table with application-specific named capabilities (default is an empty table). If the table does not contain a capability with the name 'rom', the 'rom' capability from Ned's initial caps is inserted into the table.

Less frequently used parameters:

- `l4re_dbg` An integer value overriding the debug level of the ITAS used for this application. Default is 2 (Warn). See *Debugging Flags* above.
- `ldr_flags` An integer value for setting additional flags for attaching regions, see *Loader Flags* above.

The `start()` and `startv()` calls return a task object that supports a number of operations.

- `state()` returns a string with the current task state: "running" or "zombie" if the task has terminated. If the task was already reaped (`wait()` returned) or if `kill()` was called, then the function will return `nil`.
- `exit_code()` returns the exit code if the task has terminated or `nil` if it was either killed or has been reaped.
- `kill()` forcefully terminates the task. Returns "killed" if the task was terminated or the exit code if the task was already gone. Returns `nil` if the task was already reaped.
- `exit_handler(function)` registers a Lua function that is invoked when the task terminates. If the task has already terminated, the function is called immediately. Returns `true` if the callback is pending, otherwise `false`. The callback function gets the exit code (`nil` if killed) of the task as its only parameter. The return value of the function is ignored. Only one callback can be registered.
- `wait()` suspends execution until the task has terminated. It's better to use `exit_handler()` instead. While the Lua code executes `wait()`, no `exit_handler()` will be dispatched.

#### 4.3.1.6 Reacting on task termination

Ned can react on the termination of child tasks. The preferred mechanism is to register an `exit_handler()` for a task:

```
task = L4.default_loader:start(...)
task:exit_handler(function(exit_code)
  if exit_code == nil then
    print("Task was killed")
  else
    print("Task has terminated w/ code [" .. exit_code .. "]")
  end
end)
```

If the task did already terminate then the callback is invoked immediately. It is also possible to suspend execution of the Ned script until a task has terminated:

```
task = L4.default_loader:start(...)
task:wait()
```

This method should be used with caution, though. The Ned script will wait until the child task has terminated. Neither will any of the registered `exit_handler()` will be called during this time, nor will the [remote command interface](#) be able to execute commands either.

#### 4.3.1.7 Control scheduling

Scheduling of L4Re applications is controlled by creating scheduler proxies. The proxy restricts the threads of an application to run on a subset of the available CPUs and to set their minimum and maximum priority. Use the loader factory function to create the proxy and pass it to the application:

```
sched_proxy = L4.default_loader:create_sched_proxy{ cpus=L4.Cpu_set:new("0-3") }
L4.default_loader:start({ scheduler = sched_proxy }, ...)
```

The `create_sched_proxy` function takes the following table arguments. All arguments are optional:

`cpus`: Set of allowed CPUs. Default: all CPUs. `prio_offset`: Base priority of all threads. Default: 0. `prio_limit`: Maximum priority of all threads. Default: `prio_offset + 10`. `fab`: Scheduler proxy factory capability. Default: `loader sched_fab`.

The `Cpu_set` constructor takes any number of CPU numbers or ranges:

```
Cpu_set:new()           -- all CPUs (because no argument was passed)
Cpu_set:new{}           -- empty CPU set (because an empty table was passed)
Cpu_set:new(42)          -- single CPU: 42
Cpu_set:new("0-3")       -- 4 CPUs: 0..3
Cpu_set:new("0-3", 42)   -- 5 CPUs: 0..3, 42
```

A limited number of operations are defined on CPU sets. To compute the union of two sets (all CPUs of both sets), use the `|` operator. To compute the intersection of two sets (all CPUs common to both sets), use the `&` operator.

#### 4.3.1.8 Access to the kernel debugger

Applications can enrich the kernel debugger with information using the API defined in [l4/sys/debugger](#). In order to do so, the developer has to assign access to the kernel debugger kernel object to the application. This can be done like this:

```
L4.default_loader:start({ caps = { jdb = L4.Env.jdb; }}, "rom/example")
```

### 4.3.1.9 Using the interactive ned prompt

Ned can be used in interactive mode by connecting the small ned-prompt helper tool to the command capability. Add the following code snippet at the end of your ned script:

```
local L4 = require("L4");
local l = L4.default_loader;

cmd = l:new_channel()

l:start({ log = L4.Env.log, caps = { svr = cmd } }, "rom/ned-prompt")

L4.server_loop(cmd)
```

The script hands in ned's own log capability to ned-prompt. This ensures that input and output of ned and the prompt appear on the same console.

ned-prompt needs to be added to your modules list.

## 4.3.2 Command Line Options

Ned's command line syntax is:

```
[--exit|--wait-and-exit] [--disable-backtracer-autoload] [--execute|-e STATEMENT] <lua script> [options passed]
```

Ned interprets the first non-option argument `<lua script>` as the Lua script which it should load and run. All arguments following the first non-option argument are passed as arguments to the Lua script via Lua's global `arg` table.

- Exit Options: **exit**, **wait-and-exit** (must be first if used)
  - **exit**: terminates the application after the script has run through even if there are still tasks running. `wait` for tasks at the end of the script to ensure they do not die forcefully.
  - **exit-and-wait**: terminates the application after the script has run through and all tasks started by ned have signaled their exit.
- Execute Statement Option: **execute**, **e**  
Execute the Lua statement `STATEMENT`.
- **disable-backtracer-autoload**: Do not load the backtracer automatically.

## 4.4 Io, the Io Server

The Io server handles all platform devices and resources such as I/O memory, ports (on x86) and interrupts, and grants access to those to clients.

Upon startup Io discovers all platform devices using available means on the system, e.g. on x86 the PCI bus is scanned and the ACPI subsystem initialised. Available I/O resource can also be configured via configuration scripts.

Io's configuration consists of two parts:

- the description of the real hardware
- the description of virtual buses

Both descriptions represent a hierarchical (tree) structure of device nodes. Where each device has a set of resources attached to it. And a device that has child devices can be considered a bus.

## Hardware Description

The hardware description represents the devices that are available on the particular platform including their resource descriptions, such as MMIO regions, IO-Port regions, IRQs, bus numbers etc.

The root of the hardware devices is formed by a system bus device (accessible in the configuration via `lo.system↔_bus()`). As mentioned before, platforms that support methods for device discovery may populate the hardware description automatically, for example from ACPI. On platforms that do not have support for such methods you have to specify the hardware description by hand. A simple example for this is `x86-legacy.devs`.

## Virtual Bus Description

Each lo server client is provided with its own virtual bus which it can iterate to find devices. A virtual PCI bus may be a part of this virtual bus.




Figure 4.1 IO Service Architecture Overview

The lo server must be configured to create virtual buses for its clients.

This is done with at least one configuration file specifying static resources as well as virtual buses for clients. The configuration may be split across several configuration files passed to lo through the command line.

To allow clients access to available devices, a virtual system bus needs to be created that lists the devices and their resources that should be available to that client. The names of the buses correspond to the capabilities given to lo in its launch configuration.

A very simple configuration for Io could look like this:

```
-- vim:ft=lua
-- Example configuration for io

-- Configure two platform devices to be known to io
Io.Dt.add_children(Io.system_bus(), function()

    -- create a new hardware device called "FOODEVICE"
    FOODEVICE = Io.Hw.Device(function()
        -- set the compatibility IDs for this device
        -- a client tries to match against these IDs and configures
        -- itself accordingly
        -- the list should be sorted from specific to less specific IDs
        compatible = {"dev-foo,mmio", "dev-foo"};

        -- set the 'hid' property of the device, the hid can also be used
        -- as a compatible ID when matching clients
        Property.hid = "dev-foo,Example";

        -- note: names for resources are truncated to 4 letters and a client
        -- can determine the name from the ID field of a l4vbus_resource_t
        -- add two resources 'irq0' and 'reg0' to the device
        Resource.irq0 = Io.Res.irq(17);
        Resource.reg0 = Io.Res.mmio(0x6f000000, 0x6f007fff);
    end);

    -- create a new hardware device called "BARDEVICE"
    BARDEVICE = Io.Hw.Device(function()
        -- set the compatibility IDs for this device
        -- a client tries to match against these IDs and configures
        -- itself accordingly
        -- the list should be sorted from specific to less specific IDs
        compatible = {"dev-bar,mmio", "dev-bar"};

        -- set the 'hid' property of the device, the hid can also be used
        -- as a compatible ID when matching clients
        Property.hid = "dev-bar,Example";

        -- Specify that this device is able to use direct memory access (DMA).
        -- This is needed to allow clients to gain access to DMA addresses
        -- used by this device to directly access memory.
        Property.flags = Io.Hw_device_DF_dma_supported;

        -- note: names for resources are truncated to 4 letters and a client
        -- can determine the name from the ID field of a l4vbus_resource_t
        -- add three resources 'irq0', 'irq1', and 'reg0' to the device
        Resource.irq0 = Io.Res.irq(19);
        Resource.irq1 = Io.Res.irq(20);
        Resource.reg0 = Io.Res.mmio(0x6f100000, 0x6f100fff);
    end);
end);

Io.add_vbusses
{
    -- Create a virtual bus for a client and give access to FOODEVICE
    client1 = Io.Vi.System_bus(function ()
        dev = wrap(Io.system_bus():match("dev-foo,mmio"));
    end);

    -- Create a virtual bus for another client and give it access to BARDEVICE
    client2 = Io.Vi.System_bus(function ()
        dev = wrap(Io.system_bus():match("dev-bar,Example"));
    end);
}
```

Each device supports a 'compatible' property. It is a list of compatibility strings. A client matches itself against one (or multiple) compatibility IDs and configures itself accordingly. All other device members are handled according to their type. If the type is a resource (Io.Res) it is added as a named resource. Note that resource names are truncated to 4 letters and are stored in the ID field of a [l4vbus\\_resource\\_t](#). If the type is a device it is added as a child device to the current one. All other types are treated as a device property which can be used to configure a device driver. Right now, device properties are internal to Io only.

## Matching and Assigning PCI Devices

Assigning clients PCI devices could look like this:

```
-- This is a configuration snippet for PCI device selection

local hw = Io.system_bus();

Io.add_vbusses
{
  pciclient = Io.Vi.System_bus(function ()
    PCI = Io.Vi.PCI_bus(function ()
      pci_mm      = wrap(hw:match("PCI/CC_04"));
      pci_net     = wrap(hw:match("PCI/CC_02"));
      pci_storage = wrap(hw:match("PCI/CC_01"));
    end)
  end)
}
```

The "PCI/" is followed by a bus-specific ID string. The format of the PCI ID string may be one of the following:

- PCI/CC\_cc
- PCI/CC\_ccss
- PCI/CC\_ccssp
- PCI/VEN\_vvvv
- PCI/DEV\_dddd
- PCI/SUBSYS\_sssssss
- PCI/REV\_rr
- PCI/ADR\_xxxx:xx:xx.x

Where:

- `cc` is the hexadecimal representation of the class code byte
- `ss` is the hexadecimal representation of the subclass code byte
- `pp` is the hexadecimal representation of the programming interface byte
- `vvvv` is the hexadecimal representation of the vendor ID
- `dddd` is the hexadecimal representation of the device ID
- `ssssssss` is the hexadecimal representation of the subsystem ID
- `rr` is the hexadecimal representation of the revision byte
- `xxxx:xx:xx.x` is the bus address in PCI nomenclature

As a special extension Io supports replacing the ID string with a human-readable common PCI class name. The following table gives an overview of the names known to Io and their respective PCI class and subclass.

Common Name	Description	PCI ID string
storage	Mass storage controller	CC_01
scsi	SCSI storage controller	CC_0100
ide	IDE interface	CC_0101
floppy	Floppy disk controller	CC_0102
raid	RAID bus controller	CC_0104
ata	ATA controller	CC_0105

Common Name	Description	PCI ID string
sata	SATA controller	CC_0106
sas	Serial attached SCSI controller	CC_0107
nvm	Non-volatile memory controller	CC_0108
-	-	-
network	Network controller	CC_02
ethernet	Ethernet controller	CC_0200
token_ring	Token ring network controller	CC_0201
fddi	FDDI network controller	CC_0202
atm	ATM network controller	CC_0203
isdn	ISDN controller	CC_0204
picmg	PICMG controller	CC_0206
net_infiniband	Infiniband controller	CC_0207
fabric	Fabric controller	CC_0208
network_nw	Network controller e.g. Wifi	CC_0280
-	-	-
display	Display controller	CC_03
vga	VGA compatible controller	CC_0300
xga	XGA compatible controller	CC_0301
-	-	-
media	Multimedia controller	CC_04
mm_video	Multimedia video controller	CC_0400
mm_audio	Multimedia audio controller	CC_0401
telephony	Computer telephony device	CC_0402
audio	Audio device	CC_0403
-	-	-
bridge	Bridge	CC_06
br_host	Host bridge	CC_0600
br_isa	ISA bridge	CC_0601
br_eisa	EISA bridge	CC_0602
br_microchannel	MicroChannel bridge	CC_0603
br_pci	PCI bridge	CC_0604
br_pcmcia	PCMCIA bridge	CC_0605
br_nubus	NuBus bridge	CC_0606
br_cardbus	CardBus bridge	CC_0607
br_raceway	RACEway bridge	CC_0608
br_semi_pci	Semi-transparent PCI-to-PCI bridge	CC_0609
br_infiniband_to_pci	InfiniBand to PCI host bridge	CC_060a
-	-	-
com	Communication controller	CC_07
com_serial	Serial controller	CC_0700
com_parallel	Parallel controller	CC_0701

Common Name	Description	PCI ID string
com_multiport_ser	Multiport serial controller	CC_0702
com_modem	Modem	CC_0703
com_gpib	GPiB controller	CC_0704
com_smart_card	Smart card controller	CC_0705
-	-	-
serial_bus	Serial bus controller	CC_0c
firewire	FireWire (IEEE 1394)	CC_0c00
access_bus	ACCESS bus	CC_0c01
ssa	SSA	CC_0c02
usb	USB controller	CC_0c03
fibre_channel	Fibre channel	CC_0c04
smbus	SMBus	CC_0c05
bus_infiniband	InfiniBand	CC_0c06
ipmi_smic	IPMI SMIC interface	CC_0c07
sercos	SERCOS interface	CC_0c08
canbus	CAN bus	CC_0c09
-	-	-
wireless	Wireless controller	CC_0d
bluetooth	Bluetooth	CC_0d11
w_8021a	802.1a controller	CC_0d20
w_8021b	802.1b controller	CC_0d21

### Strong Matching of PCI Devices

If more specific matching of PCI devices is required it is possible to concatenate multiple ID strings using &. An example where a specific device from a specific vendor at a fixed bus address is matched would use the string `PCI/VEN_vvvv&DEV_dddd&ADR_xxxx:xx:xx.x`.

### Isolation of PCIe devices

PCIe encodes device communication with a network-like protocol with destination headers and packet fragmentation allowing a devices to talk directly to other devices. This potentially works against security boundaries for a system. E.g. two network cards could exchange packets and thereby leak information from one security domain to the other without involvement of the OS.

PCIe introduced an optional capability named PCI Access Control Services (PCI/ACS) to control communication between PCIe devices.

With PCI/ACS it is possible to restrict inter-device communication between PCIe devices.

PCI/ACS is optional and for Intel chipsets, it is usually only implemented on high-end PCI platform controller hubs (PCHs), and is missing on low-end and mobile PCHs. On some Intel-PCHs there exist facilities that allow for similar isolation.

If IO encounters a supported PCH, it will enable those facilities in order to enforce device isolation.



## Command Line Options

The lo Server supports the following optional parameters:

```
[--verbose|v] [--transparent-msi] [--trace <trace_mask>] [--acpi-debug-level <debug_level>] [config_files]
```

- **verbose|v**

By default, error debug messages are enabled. This option increments the verbosity level, and can be applied multiple times to reach the desired debug level. The available debug levels are ordered as: `DBG_ERR` (default, level 1), `DBG_WARN`, `DBG_INFO`, `DBG_DEBUG`, `DBG_DEBUG2` and `DBG_ALL` (level 6).

- **transparent-msi**

Enable MSI on PCI devices which support this feature. This is transparent to clients, as there are no changes in the API used to interact with PCI device via interrupts.

- **acpi-debug-level <level\_mask>**

Set the ACPI debug level. The `<level_mask>` is a mask that selects components of interest for debugging. It can be constructed from the ACPI debug constants defined in the linux kernel, see [ACPI Debug Output](#) for details. By default, the ACPI debug level is set to `ACPI_LV_INIT | ACPI_LV_TABLES | ACPI_LV_VERBOSE_INFO`.

- **trace <trace\_mask>**

Enable tracing of events matching `trace_mask`. The only supported trace mask is 1 and this matches ACPI events.

- **config\_files**

Space separated list of Lua configuration files specifying real hardware and virtual buses. See example on [Virtual Bus Description](#).

## 4.5 Virtio Net P2P, a virtual network point-to-point link

The virtual network point-to-point server (p2p) connects two clients with a virtual network connection. It uses virtio as the transport mechanism. Each virtual network p2p endpoint implements the device-side of a virtio network device. Each client can access its endpoint using the driver-side semantics of a virtio network device.

## Capabilities

- **dataspace**

Trusted dataspaces

Multiple capability names can be provided by the `--register-ds` command line parameter.

- **svr**

Server Capability of application. Endpoint for IPC calls

Mandatory capability.

## Command Line Options

The following command line options are supported:

- `-p <num_usec>, --poll <num_usec>`  
 Enable polling mode and set the poll interval. IRQ notification is disabled for queues while in polling mode.  
 Numerical value.
  - Must be a positive integer specified in microseconds.
- `-s <num>, --size <num>`  
 Set the maximum queue size for the device-side virtio queues.  
 Numerical value.
  - Must be a power of 2 in the range of 1 to 32768 inclusive.
 Default: 256
- `-d <cap_name>, --register-ds <cap_name>`  
 Register a trusted dataspace capability. If this option is used, it is not possible to communicate with the server via dataspaces other than the registered ones.  
 Can be used multiple times.  
 Name of a provided capability that adheres to the dataspace protocol.

## Building and Configuration

The virtual network p2p server can be built using the [L4Re](#) build system by placing this project into the `pkg` directory.

## Starting the service

The virtual network p2p server can be started with Lua like this:

```
local p2p = L4.default_loader:new_channel();
L4.default_loader:start(
{
  caps = {
    svr = p2p:svr(),
  },
},
"rom/l4vio_net_p2p [<options>]");
```

First an IPC gate (`p2p`) is created which is used between the virtual network p2p server and a client to create new virtual ports. The server-side is assigned to the mandatory `svr` capability of the virtual network p2p server. See the section below on how to create a new virtual port and connect a client to it.

## Virtual p2p port

Prior to connecting a client to a virtual network p2p server port it has to be created using the following Lua function. It has to be called on the client side of the IPC gate capability whose server side is bound to the virtual network p2p server.

The "key=value" pairs passed to create() can be omitted and their order is not important.

Call: `create(0 [, "ds-max=<max>", "mac=<addr>"])`

- "ds-max=<max>"

Specifies the upper limit of the number of dataspace the client is allowed to register with the server for virtio DMA.

Numerical value.

- Must be in the range of 1 to 80 inclusive.

Default: 2

- "mac=<addr>"

Specify the MAC address of the endpoint where <mac\_address> is of the form xx:xx:xx:xx:xx:xx.

String value.

- Must be in the form xx:xx:xx:xx:xx:xx.

If the `create()` call is successful a new capability which references a virtual network p2p server port is returned. A client uses this capability to talk to the virtual network p2p server using the virtio network protocol.

## Examples

A couple of examples on how to create ports with different properties are listed below.

```
-- two normal ports with at most 4 data spaces
net0 = p2p:create(0, "ds-max=4")
net1 = p2p:create(0, "ds-max=4")
-- normal port with 4 data spaces and MAC address
net0 = p2p:create(0, "ds-max=4", "mac=11:22:33:44:55:66")
```

## 4.6 Virtio Net Switch, a virtual network switch

The virtual network switch connects multiple clients with a virtual network connection. It uses Virtio as the transport mechanism. Each virtual switch port implements the host-side of a Virtio network device (virtio-net).

### Capabilities

- `dataspace`

Trusted dataspace

Multiple capability names can be provided by the `--register-ds` command line parameter.

- `svr`

Server Capability of application. Endpoint for IPC calls

Mandatory capability.

## Command Line Options

In the example above the virtual network switch is started in its default configuration with a maximum of 5 virtual ports. To customize the configuration the virtual network switch accepts the following command line options:

- `-D <component=level>, --debug <component=level>`  
 Configure individual debug levels per component. Verbosity increases from `quiet` up to `trace`.  
 Can be used multiple times.  
 Possible values for component are | `core, virtio, port, request, queue, packet`.  
 Possible values for level are | `quiet, warn, info, debug, trace`.
- `-m, --mac`  
 Ignored. Provided for compatibility with older switch versions.  
 Flag. True if provided.
- `-M`  
 Do not assign a random MAC address to ports by default. It is always possible to set an explicit MAC address by passing the `mac=` to the factory call, regardless of this option. If `-M` is passed and no `mac=` address was given, it is the responsibility of the Virtio driver to choose an appropriate address.  
 Flag. True if provided.
- `-p <num>, --ports <num>`  
 Set the maximum number of virtual ports.  
 Numerical value.  
 Default: 256
- `-q, --quiet`  
 Silence all output except for error messages.  
 Flag. True if provided.
- `-s <num>, --size <num>`  
 Set the maximum queue size for the device-side Virtio queues.  
 Numerical value.
  - Must be a power of 2 in the range of 1 to 32768 inclusive.
 Default: 256
- `-v, --verbose`  
 Increase the global verbosity level. Individual levels per component can be set using the `-D` option.  
 Can be used up to 3 times.  
 Flag. True if provided.
- `-d <cap_name>, --register-ds <cap_name>`  
 Register a trusted dataspace capability. If this option gets used, it is not possible to communicate with the server via dataspace other than the registered ones. Can be used multiple times for multiple dataspace.  
 The option's parameter is the name of a dataspace capability.  
 Can be used multiple times.  
 Name of a provided capability that adheres to the dataspace protocol.

The virtual network switch can be setup to feature exactly one monitor port. All traffic passing through the switch is mirrored to the monitor port. The monitor port is read-only, and has no TX capability. An optional packet filter can be configured and implemented to filter data sent to the monitor port.

## Configuration

Certain features of the virtual network switch are configurable at compile-time. Configuration is done through the build-time configuration of the [L4Re](#) build tree.

## Starting the service

The virtual network switch can be started in Ned like this:

```
local switch = L4.default_loader:new_channel();
L4.default_loader:start(
{
  caps = {
    svr = switch:svr(),
  },
},
"rom/l4vio_switch");
```

First a communication channel (`switch`) is created which is used to create virtual network ports. It is connected to the switch component via its mandatory `svr` capability. See the section below on how to create a new virtual port and connect a client to it.

## Hardware devices

To plug hardware devices into the switch, provide a `Vbus` capability with the name `vbus` when starting the switch. To use this feature, you have to enable the `VNS_IXL` config option.

## Virtual switch port

First, a virtual network port has to be created using the following Ned-Lua function. It has to be called on the communication channel called `switch`, which has been created earlier.

```
Call: create(0 [, "ds-max=<max>", "name=<name>", "type=<port type>", "vlan=(access=<vlan id>|trunk=<vlan id>[,<vlan id>]*)", "mac=<addr>"])
```

- "ds-max=<max>"

Specifies the upper limit of the number of dataspace the client is allowed to register with the virtual network switch for Virtio DMA.

Numerical value.

- In the range of 1 to 80 inclusive

- "name=<name>"

Sets the name of port in debug messages to `<name>`. A name may consist of at most 19 characters, all other characters are dropped. If there is enough space left, the name will get a postfix of "`[<port number>]`", e.g. "name=foo" -> foo[1].

String value.

- "type=<port type>"

Optionally specify the port type.

Possible values for `<port type>` are

- monitor: Monitor Port
- normal: Normal Port

Default: normal

- "vlan=(access=<vlan id>|trunk=<vlan id>[,<vlan id>]\*)"

Configure the port to participate in an IEEE 802.1Q compatible VLAN. Fundamentally there are two types of ports: access ports and trunk ports.

The Value for this parameter can be one of the following:

- "access=<vlan id>"

Configures the port as access port for VLAN <vlan id> where the id must be a decimal number greater than 0 and less than 4095 in accordance to the standard. Packets on an access port belong to the configured VLAN and are only forwarded to ports that belong to the same VLAN or trunk ports that participate in the particular VLAN. The packets on this port will not have a VLAN tag attached to them so that a guest connected to this port does not see that the port is part of a VLAN.

An optional monitor port will see packets from an access port as VLAN tagged packets with the <vlan id> given for the port.

Numerical value.

- \* In the range of 0 to 4095 exclusive

- "trunk=<vlan id>[, <vlan id>]\*"

Configures the port as trunk port. It participates either in all VLANs, if specified by the keyword 'all', or in the list of VLANs given as comma separated list. There must be no whitespace in the list. Each id must be a decimal number greater than 0 and less than 4095 in accordance to the standard. Outgoing packets on this port will be tagged with an IEEE 802.1Q compatible tag. Incoming packets must be tagged with a VLAN tag from the given list. Packets that have no tag or a tag not in the vlan id list are dropped silently. They are not forwarded to the monitor port either. Currently there is no support for IEEE 802.1p. The PCP and DEI sub-fields in the TCI field will be set to zero on outgoing packets and are ignored for incoming packets.

Numerical value.

- "mac=<addr>"

Explicitly sets the MAC address of the port. It will be checked that no other port on the switch has the same address. It is the responsibility of the user to ensure the validity of the address and its global uniqueness, though.

String value.

- In form xx:xx:xx:xx:xx:xx

If the `create()` call is successful a new capability which references a virtual switch port is returned. A client uses this capability to talk to the virtual network switch using the Virtio network protocol.

## Examples

Here are couple of examples on how to create ports with different properties:

```
-- normal port with at most 4 data spaces
net0 = switch:create(0, "ds-max=4")
-- like the previous but with name foo
net0 = switch:create(0, "ds-max=4", "name=foo")
-- like the previous but the port is a monitor port
net0 = switch:create(0, "ds-max=4", "name=foo", "type=monitor")
-- normal port with 4 data spaces as access port to VLAN 1
net0 = switch:create(0, "ds-max=4", "name=v11", "vlan=access=1")
-- normal port with 4 data spaces as trunk port participating in VLAN 1 & 2
net0 = switch:create(0, "ds-max=4", "name=v11", "vlan=trunk=1,2")
```

## 4.7 Uvmm, the virtual machine monitor

Uvmm provides a virtual machine for running an unmodified guest in non- privileged mode.

## Capabilities

- `ram`

The memory for the guest provided via a simple dataspace.

- `pfc`

Uvmm can be instructed to inform a PM manager of PM events through the [L4::Platform\\_control](#) interface. To that end, uvmm may be equipped with a `pfc` cap. On suspend, uvmm will call [l4\\_platform\\_ctl\\_system\\_suspend\(\)](#).

The `pfc` cap can also be implemented by IO. In that case the guest can start a machine suspend/shutdown/reboot.

## Command Line Options

- `--mon <option>`

Control the handling of guest reads/writes to non-existing memory.

Possible values for `<option>` are

- `true`: The monitor interface is enabled but no server implementing the client side of the monitor interface is started. The monitor interface can still be utilized via cons but no readline functionality will be available.
- `some_binary`: If a string is passed as the value of `mon`, the monitor interface is enabled and the string is interpreted as the name of a server binary which implements the client side of the monitor interface. This server is automatically started and has access to a `vcon` capability named `mon` at startup through which it can make use of the monitor interface. Unless you have written your own server you should specify `'uvmm_cli'` which is a server implementing a simple readline interface.
- `false`: The monitor interface is disabled at runtime.

Default: `true`

- `-c <guest command line>,--cmdline <guest command line>`

Command line that is passed to the guest on boot.

String value.

- `-k <kernel image name>,--kernel <kernel image name>`

The name of the guest-kernel image file present in the ROM namespace.

File path in ROM namespace.

- `-d <DTB overlay>,--dtb <DTB overlay>`

The name of the device tree file present in the ROM namespace. The device tree will be placed in the upmost region of guest memory. Optionally, a user may use an additional parameter in the form of "`<DTB overlay>:limit=0xffffffff`" to set an upper limit for the device tree location.

This option can be issued multiple times. uvmm will merge all provided device tree overlays.

File path in ROM namespace.

- `-r <RAM disk name>,--ramdisk <RAM disk name>`

The name of the RAM disk file present in the ROM namespace

File path in ROM namespace.

- `-b <Base address of the guest RAM>,--rambase <Base address of the guest RAM>`

Physical start address for the guest RAM. This value is platform specific.

Numerical value.

- `-D <component=level>, --debug <component=level>`

Control the verbosity level of the uvmm.

Using the `component` prefix, the verbosity level of each uvmm component is configurable.

For example, the following command line sets the verbosity of all uvmm components to `info` except for IRQ handling, which is set to `trace`:

```
uvmm -D info -D irq=trace
```

Can be used multiple times.

Possible values for `component` are | `core, cpu, mmio, irq, dev, pm, vbus_event`.

Possible values for `level` are | `quiet, warn, info, trace`.

Options `-q, --quiet, -v, --verbose` and `-D, --debug` cancel each other out.

- `-f, --fault-mode`

Control the handling of guest reads/writes to non-existing memory.

Possible values are

- `ignore`: Invalid writes are ignored. Invalid reads either return 0 or are skipped. The guest may experience undefined behaviour.
- `halt`: Halt the VM on the first invalid memory access.
- `inject`: Try to forward the invalid access to the guest. This is not supported on all architectures. Falls back to `halt` if the error could not be forwarded to the guest.

Default: `ignore`

- `-q, --quiet`

Silence all uvmm output.

Flag. True if provided.

Options `-q, --quiet, -v, --verbose` and `-D, --debug` cancel each other out.

- `-v, --verbose`

Increase the verbosity of the uvmm. Repeating the option increases the verbosity by another level.

Can be used multiple times.

Flag. True if provided.

Options `-q, --quiet, -v, --verbose` and `-D, --debug` cancel each other out.

- `-W, --wakeup-on-system-resume`

When set, the uvmm resumes when the host system resumes after a suspend call.

Flag. True if provided.

- `-i, --ram-identity-mapping`

When set, the option forces the guest RAM to be mapped to its corresponding host-physical addresses.

Flag. True if provided.

## Setting up guest memory

In the most simple setup, memory for the guest can be provided via a simple dataspace. In your ned script, create a new dataspace of the required size and hand it into uvmm as the `ram` capability:

```
local ramds = L4.Env.user_factory:create(L4.Proto.Dataspace, 0x4000000)

L4.default_loader::startv({caps = {ram = ramds:m("rw")}}, "rom/uvmm")
```

The memory will be mapped to the most appropriate place and a memory node added to the device tree, so that the guest can find the memory.



For a more complex setup, the memory can be configured via the device tree. uvmm scans for memory nodes and tries to set up the memory from them. A memory device node should look like this:

```
memory@0 {
    device_type = "memory";
    reg = <0x00000000 0x00100000
          0x00200000 0xffffffff>;
    l4vmm,dscap = "memcap";
    dma-ranges = <>;
};
```

The `device_type` property is mandatory and needs to be set to `memory`.

`l4vmm,dscap` contains the name of the capability containing the dataspace to be used for the RAM. `reg` describe the memory regions to use for the memory. The regions will be filled up to the size of the supplied dataspace. If they are larger, then the remaining area will be cut.

If the optional `dma-ranges` property is given, the host-physical address ranges for the memory regions will be added here. Note that the property is not cleared first, so it should be left empty.

For more details see [RAM configuration](#).

## Memory layout

uvmm populates the RAM with the following data:

- kernel binary
- (optional) ramdisk
- (optional) device tree

The kernel binary is put at the predefined address. For ELF binaries, this is an absolute physical address. If the binary supports relative addressing, the binary is put to the requested offset relative to beginning of the first 'memory' region defined in the device tree.

The ramdisk and device tree are placed as far as possible to the end of the regions defined in the first 'memory' node.

If there is a part of RAM that must remain empty, then define an extra memory node for it in the device tree. uvmm only writes to memory in the first memory node it finds.

Warning: uvmm does not touch any unpopulated memory. In particular, it does not ensure that the memory is cleared. It is the responsibility of the provider of the RAM dataspace to make sure that no data leakage can happen. Normally this is not an issue because dataspaces are guaranteed to be cleaned when they are newly created but users should be careful when reusing memory or dataspaces, for example, when restarting the uvmm.

## Forwarding hardware resources to the guest

Hardware resources must be specified in two places: the device tree contains the description of all hardware devices the guest could see and the Vbus describes which resources are actually available to the uvmm.

The vbus allows the uvmm access to hardware resources in the same way as any other [L4](#) application. uvmm expects a capability named 'vbus' where it can access its hardware resources. It is possible to leave out the capability for purely virtual guests (Note that this is not actually practical on some architectures. On ARM, for example, the guest needs hardware access to the interrupt controller. Without a 'vbus' capability, interrupts will not work.) For information on how to configure a vbus, see the [IO documentation](#).

The device tree needs to contain the hardware description the guest should see. For hardware devices this usually means to use a device tree that would also be used when running the guest directly on hardware.

On startup, uvmm scans the device tree for any devices that require memory or interrupt resources and compares the required resources with the ones available from its vbus. When all resources are available, it sets up the appropriate forwarding, so that the guest now has direct access to the hardware. If the resources are not available, the device will be marked as 'disabled'. This mechanism allows to work with a standard device tree for all guests in the system while handling the actual resource allocation in a flexible manner via the vbus configuration.

The default mechanism assigns all resources 1:1, i.e. with the same memory address and interrupt number as on hardware. It is also possible to map a hardware device to a different location. In this case, the assignment between vbus device and device tree device must be known in advance and marked in the device tree using the `l4vmm, vbus-dev` property.

The following device will for example be bound with the vbus device with the HID 'l4-test,dev':

```
test@e0000000 {
    compatible = "memdev,bar";
    reg = <0 0xe0000000 0 0x50000>,
        <0 0xe1000000 0 0x50000>;
    l4vmm,vbus-dev = "l4-test,dev";
    interrupts-extended = <&gic 0 139 4>;
};
```

Resources are then matched by name. Memory resources in the vbus must be named `reg0` to `reg9` to match against the address ranges in the device tree `reg` property. Interrupts must be called `irq0` to `irq9` and will be matched against `interrupts` or `interrupts-extended` entries in the device tree. The vbus must expose resources for all resources defined in the device tree entry or the initialisation will fail.

An appropriate IO entry for the above device would thus be:

```
MEM = Io.Hw.Device(function()
    Property.hid = "l4-test,dev"
    Resource.reg0 = Io.Res.mmio(0x41000000, 0x4104ffff)
    Resource.reg1 = Io.Res.mmio(0x42000000, 0x4204ffff)
    Resource.irq0 = Io.Res.irq(134);
end)
```

Please note that HIDs on the vbus are not necessarily unique. If multiple devices with the HID given in `l4vmm, vbus-dev` are available on the vbus, then one device is chosen at random.

If no vbus device with the given HID is available, the device is disabled.

## How to enable guest suspend/resume

### Note

Currently only supported on ARM. It should work fine with Linux version 4.4 or newer.

Uvmm (partially) implements the power state coordination interface (PSCI), which is the standard ARM power management interface. To make use of this interface, you have to announce its availability to the guest operating system via the device tree like so:

```
psci {
    compatible = "arm,psci-0.2";
    method = "hvc";
};
```

The Linux guest must be configured with at least these options:

```
CONFIG_SUSPEND=y
CONFIG_ARM_PSCI=y
```

## How to communicate power management (PM) events

Uvmm can be instructed to inform a PM manager of PM events through the [L4::Platform\\_control](#) interface. To that end, uvmm may be equipped with a `pf_c` cap. On suspend, uvmm will call `l4_platform_ctl_system_suspend()`.

The `pf_c` cap can also be implemented by IO. In that case the guest can start a machine suspend/shutdown/reboot.

## Ram block device support

The example ramdisk works by loading a file system into RAM, which needs RAM block device support to work. In the Linux kernel configuration add: `CONFIG_BLK_DEV_RAM=y`

## Framebuffer support for uvmm/amd64 guests

Uvmm can be instructed to pass along a framebuffer to the Linux guest. To enable this three things need to be done:

1. Configure Linux to support a simple framebuffer by enabling

```
CONFIG_FB_SIMPLE=y
CONFIG_X86_SYSFB=y
```

2. Configure a simple framebuffer device in the device tree (currently only read by uvmm, linearer framebuffer at [0xf0000000 - 0xf1000000])

```
simplefb {
    compatible = "simple-framebuffer";
    reg = <0x0 0xf0000000 0x0 0x1000000>;
    l4vmm,fbcap = "fb";
};
```

3. Start a framebuffer instance and connect it to uvmm e.g.

```
-- Start fb-drv (but only if we need to)
local fbdrv_fb = L4.Env.vesa;
if (not fbdrv_fb) then
    fbdrv_fb = l:new_channel();
    l:start({
        caps = {
            vbus = io_busses.fbdrv,
            fb   = fbdrv_fb:svr(),
        },
        log = { "fbdrv", "r" },
    },
    "rom/fb-drv");
end
vmm.start_vm{
    ext_caps = { fb = fbdrv_fb },
    -- ...
```

## Requirements on the Fiasco.OC configuration on amd64

The kernel configuration must feature `CONFIG_SYNC_TSC=y` in order for the emulated timers to reach a sufficiently high resolution.

## Recommended Linux configuration options for uvmm/amd64 guests

The following options are recommended in addition to the amd64 defaults provided by a `make defconfig`:

Virtio support is required to access virtual devices provided by uvmm:

```
CONFIG_VIRTIO=y
CONFIG_VIRTIO_PCI=y
CONFIG_VIRTIO_BLK=y
CONFIG_BLK_MQ_VIRTIO=y
CONFIG_VIRTIO_CONSOLE=y
CONFIG_VIRTIO_INPUT=y
CONFIG_VIRTIO_NET=y
```

It is highly recommended to use the X2APIC, which needs virtualization awareness to work under uvmm:

```
CONFIG_X86_X2APIC=y
CONFIG_PARAVIRT=y
CONFIG_PARAVIRT_SPINLOCKS=y
```

## KVM clock for uvmm/amd64 guests

When executing [L4Re](#) + uvmm on QEMU, the PIT as clock source is not reliable. The paravirtualized KVM clock provides the guest with a stable clock source.

A KVM clock device is available to the guest, if the device tree contains the corresponding entry:

```
kvm_clock {
    compatible = "kvm-clock";
    reg = <0x0 0x0 0x0 0x0>;
};
```

To make use of this clock, the Linux guest must be built with the following configuration options:

```
CONFIG_HYPERVISOR_GUEST=y
CONFIG_KVM_GUEST=y
CONFIG_PTP_1588_CLOCK_KVM is not set
```

### Note

KVM calls besides the KVM clock are unhandled and lead to failure in the uvmm, e.g. `vmcall 0x9` for the `PTP_1588_CLOCK_KVM`.

This is considered a development feature. The KVM clock is not required when running on physical hardware as TSC calibration via the PIT works as expected.

## Development notes for amd64

When you are developing on Linux using QEMU please note that nested virtualization support is necessary on your host system to run uvmm guests. Your host Linux version should be 4.12 or greater, **excluding 4.20**.

Check if your KVM module has nested virtualization enabled via:

```
cat /sys/module/kvm_intel/parameters/nested
Y
```

In case it shows N instead of Y enable nested virtualization support via:

```
modprobe kvm_intel nested=1
```

On AMD platforms the module name is `kvm_amd`.

## QEMU network setup for a uvmm guest on amd64

```
qemu-system-x86_64 -M q35 -cpu host -enable-kvm -device intel-iommu
                  -device e1000e,netdev=net0 -netdev bridge,id=net0,br=virbr0
```

where 'virbr0' is the name of the host's bridge device. The line 'allow virbr0' needs to be present in /etc/qemu/bridge.conf. The bridge can either be created via the network manager or via the command line:

```
brctl addbr virbr0
ip addr add 192.168.124.1/24 dev virbr0
ip link set up dev virbr0
```

In the guest linux with eth0 as network device:

```
ip a a 192.168.124.5/24 dev eth0
ip li se up dev eth0
```

Now the host and guest can ping each other using their respective IPs.

Of course, uvmm needs to be connected to io and io needs a vbus configuration for the uvmm client like this:

```
Io.add_vbusses
{
    vm_pci = Io.Vi.System_bus(function ()
        Property.num_msis = 6
        PCI = Io.Vi.PCI_bus(function ()
            pci_net = wrap(Io.system_bus():match("PCI/CC_0200"))
        end)
    end)
}
```

## QEMU emulated VirtIO devices and IO-MMU on amd64

QEMU does not route VirtIO devices through the IO-MMU per default. To use QEMU emulated VirtIO devices add the `disable-legacy=on,disable-modern=off,iommu_platform=on` flags to the option list of the device. The e1000e card in the network example above can be replaced with an virtio-net-pci card like this:

```
-device virtio-net-pci,disable-legacy=on,disable-modern=off,
      iommu_platform=on,netdev=net0
```

For more information on VirtIO devices and their options see <https://wiki.qemu.org/Features/VT-d>.

## Using the uvmm monitor interface

Uvmm implements an interface with which parts of the guest's state can be queried and manipulated at runtime. This monitor interface needs to be enabled during compilation as well as during startup of uvmm. This is described in detail below.

### Compiling uvmm with monitor interface support

To compile uvmm with monitor interface support pass the `CONFIG_MONITOR=y`, option during the `make` step (or set in in the Makefile.config). This option is available on all architectures but note that the set of available monitor interface features may vary significantly between them. Also note that the monitor interface will always be disabled in release mode, i.e. if `CONFIG_RELEASE_MODE=y`.

## Enabling the monitor interface at runtime

When starting a uvmm instance from inside a `ned` script using the `uvmm.start_vm` function, the `mon` argument controls whether the monitor interface is enabled at runtime. There are three cases to distinguish:

- `mon=true` (default): The monitor interface is enabled but no server implementing the client side of the monitor interface is started. The monitor interface can still be utilized via `cons` but no readline functionality will be available.
- `mon='some_binary'`: If a string is passed as the value of `mon`, the monitor interface is enabled and the string is interpreted as the name of a server binary which implements the client side of the monitor interface. This server is automatically started and has access to a `vcon` capability named `mon` at startup through which it can make use of the monitor interface. Unless you have written your own server you should specify `'uvmm_cli'` which is a server implementing a simple readline interface.
- `mon=false`: The monitor interface is disabled at runtime.

## Using the monitor interface

If the monitor interface was enabled you can connect to it via `cons` under the name `mon<n>` where `<n>` is a unique integer for every uvmm instance that is started with the monitor interface enabled (numbered starting from one in order of corresponding `uvmm.start_vm` calls). If `mon='uvmm_cli'` was specified, readline functionality such as command completion and history will be available. Enter a command followed by enter to run that command. To obtain a list of all available commands issue the `help` command, to obtain usage information for a specific command `foo` issue `help foo`.

### Note

Some commands will modify the guests state. Since it should be obvious to which ones this applies this is usually not specifically highlighted. Exercise reasonable caution.

## Using the guest debugger

The guest debugger provides monitoring functionality akin to a very bare-bone GDB interface, e.g. guest RAM and page table dumping, breakpointing and single stepping. Additional functionality might be added in the future.

### Note

The guest debugger is currently still under development. The guest debugger may also not be available on all architectures. To check whether the guest debugger is available check if `help dbg` returns usage information.

If the guest debugger is available, you have to manually load it at runtime using the monitor interface. This saves resources if the guest debugger is not used. To enable the guest debugger, issue the `dbg on` monitor command. Once enabled, the guest debugger can not be disabled again.

To list available guest debugger subcommands, issue `dbg help` after `dbg on`.

### Note

When using SMP, most guest debugger subcommands require you to explicitly specify a guest vcpu using an index starting from zero.

### 4.7.1 RAM configuration

#### RAM configuration for uvmm

##### Without a memory node in the device tree

- setup default RAM for guest VM.
- RAM starts either
  - at base-address which defaults to 0x0 or the base address value set via the -b cmdline option or
  - in case of identity mapping at the host-physical address of the dataspace allocated for the RAM

##### With a memory node in the device tree

The memory node needs at least the properties `device_type` and `l4vmm,dscap`:

```
memory@0 {  
    device_type = "memory";  
    l4vmm,dscap = "ram";  
}
```

Where the given `l4vmm,dscap` name is accessible in the capability namespace of the uvmm. If the capability is invalid, the memory node is disabled.

If memory nodes are given, but none provides valid RAM the configuration is invalid and uvmm refuses to boot.

Additional properties of the memory node are `reg` and `dma-ranges`.

The `reg` property describes the location in the guest's address space that should be backed by RAM.

The `dma-ranges` property describes the offset between guest-physical and host-physical addresses. The guest can evaluate this non-standard property to derive the correct DMA addresses to program into passed-through devices. Usage of this property **requires** modification of guest code.

##### Without `reg` and `dma-ranges` properties

The `reg` property is optional only in case the uvmm maps the guest's RAM into the VM under the host-physical addresses of the backing memory (`l4vmm,dscap`).

This case can be forced via the cmdline parameter `-i` and is the default for platforms without IOMMU, but with DMA capable devices on the configured vBus.

##### Without a `reg` property, but with a `dma-ranges` property

If the `-i` cmdline parameter is given, identity mapping is forced and the behavior is the same as in the case above. Additionally, the `dma-ranges` property is written

In case no `-i` cmdline parameter is given, the configuration is invalid and uvmm refuses to boot.

### With a reg property

uvmm parses the reg property of the memory node and maps the memory into the VM to the given range(s).

If the -i cmdline parameter is set, the reg property is ignored and the memory is mapped into the VM under the corresponding host-physical addresses of the backing memory (l4vmm,dscap)

### With a reg and dma-ranges property

uvmm parses the reg property of the memory node and maps the memory into the VM to the given range(s).

The dma-ranges property is filled with the corresponding host-physical addresses of the backing memory (l4vmm,dscap).

## 4.8 RTC driver

The RTC driver can drive various real-time clocks and provides an interface for other components, e.g., uvmm, to read and write the time.

It needs access to the hardware, depending on the clock, either via a vbus or via an I2C device.

### Command Line Options

There are no command line options.

### Environment

Several capabilities can be used to interact with the environment:

- 'rtc' (server)  
The capability with which clients talk to the service. Note that writing to the RTC is only possible when having the rtc capability with write rights, read-only clients must have the capability with read rights only.
- 'vbus'  
The vbus used to access hardware for port-based clock on X86 and pl031 on arm.  
The vbus is also needed for receiving the inhibitor signal from IO.
- 'ds3231' (optional)  
The capability that provides access to an I2C DS3231 device. The capability needs to be created with type 1 (i2c-device).

## 4.9 Mag, the GUI Multiplexer

Mag is the default multiplexer for graphics hardware. Mag is a Nitpicker derivate that allows secure multiplexing of the graphics and input hardware among multiple applications and multiple complete windowing environments. It is not, and does not attempt to be, a fully-fledged window manager.



## Capabilities

None.

## Command Line Options

The following command line options are supported:

```
<$FILE.lua | libmag-$LIBNAME.so>
```

As Mag's only command line option it supports loading additional plugins via the application's command line.

Can be used multiple times.

File path in ROM namespace.

- Plugins must be either a Lua file or a shared library. Shared libraries must be named libmag-\$LIBNAME.so.

## Session Factory

As a simple nitpicker clone Mag supports the so-called Xray mode. This mode displays all session labels and draws a colored frame around them. The session that currently has the input focus is highlighted. The Xray mode is activated via the special keys Scroll or NEXTSONG.

Call: `create(0 [, "label|l=<LABEL>", "col=(string|hex)"])`

- "label|l=<LABEL>"

Set the session's text label to LABEL.

String value.

- The label is restricted to a length of 256 characters.

- "col=(string|hex) "

Set the session's color which is used in Xray mode to tint the session's screen area and the border drawn around it. The argument can be either one of the following letters or a hexadecimal representation of the RGB values.

The Value for this parameter can be one of the following:

- string

Define the color by the given character

Possible values are

- \* r, R: Red color
- \* g, G: Green color
- \* b, B: Blue color
- \* w, W: White color
- \* y, Y: Yellow color
- \* v, V: Magenta color

- hex

Define the color by its RGB values in hexadecimal representation.

Hexadecimal number without '0x' prefix.

## Mag Client Session

A client with a mag client session gets access to the whole screen. The client has to allocate and manage its own buffers and has to position them on the screen on its own.

Call: `create(L4.Proto.Goos [, "default-background|dfl-bg"])`

- "default-background|dfl-bg"  
Marks this session as the default background.  
Flag. True if provided.

## Mag Client Framebuffer Session

For a client framebuffer session mag allocates a view of the requested size and displays it at the requested coordinates on the screen.

Call: `create(L4.Proto.Goos [, "geometry|g=<GEOMETRY>", "focus", "shaded", "fixed", "barheight=<X>"])`

- "geometry|g=<GEOMETRY>"  
Set the session's geometry and position on the screen. GEOMETRY is provided in an X11-style format: WIDTHxHEIGHT+X\_OFFSET+Y\_OFFSET.  
String value.
- "focus"  
Set the focus to this session.  
Flag. True if provided.
- "shaded"  
The window is collapsed and only the title bar is visible. The window can be expanded by clicking into the title bar with the middle mouse button. Collapsing and expanding works also independently of this option.  
Flag. True if provided.
- "fixed"  
The window cannot be moved on the screen.  
Flag. True if provided.
- "barheight=<X>"  
Set the height of the title bar in pixels.  
Numerical value.

## Examples

### Creating a session

```
-- set label to "Linux" and use a light blue color
fb = mag_client:create(L4.Proto.Goos, "l=Linux", "col=98d9ff");
```

**Requesting a framebuffer via a client framebuffer session**

```
-- create a window of 640x480 pixels at position (100,100) on the screen.
fb = mag_fb:create(L4.Proto.Goos, "g=640x480+100+100");
```

## 4.10 Cons, the Console Multiplexer

`cons` is an interactive multiplexer for console input and output. It buffers the output from different L4 clients and allows to switch between them to redirect input.

### Multiplexers and Frontends

`cons` is able to connect multiple clients to multiple console I/O servers. All clients are connected to all configured multiplexers

Multiplexers and frontends come in pairs where the actual I/O is handled by the frontend. From the point-of-view of `cons`, a frontend consists of an IPC channel to a server that speaks an appropriate server protocol. By default the `L4.Env.log` capability is used. Only frontends that speak the `L4::Vcon` protocol are supported.

A multiplexer handles and routes the I/O of each client to and from its respective frontend.

Each client's console settings (e.g. color, visibility) apply to all multiplexers and cannot be changed individually. A user can connect to all clients through all multiplexers. It is not possible to assign individual clients to distinct multiplexers.

### Client sessions

For clients `cons` implements the `L4::Vcon` and the Virtio console interface. A client session can be requested through a `create` call to `cons`'s factory. `cons` binds its factory capability to the `cons` capability. See the example below on how this can be set up.

### Starting the service

The `cons` server can be started with Lua like this:

```
local log_server = L4.default_loader:new_channel()
L4.default_loader:start({
  caps = {
    cons = log_server:svr(),
  },
  log = L4.Env.log,
},
"rom/cons")
```

First an IPC gate (`log_server`) is created which is used between the `cons` server and a client to request a new session. The server side is assigned to the mandatory `cons` capability of `cons`. This example explicitly assigns the kernel's log capability (`L4.Env.log`) to `cons`'s `log` capability in order to allow `cons` to provide input and output for its clients. The default log factory (usually provided by `moe`) doesn't provide input capabilities.

## Command Line Options

cons accepts the following command line switches:

- `-a, --show-all`  
Initially show output from all clients.
- `-B <size>, --defaultbufsize <size>`  
Default buffer size per client in bytes. Default: 40960
- `-c <client>, --autoconnect <client>`  
Automatically connect to the client with the given name. That means that output of this client will be visible and input will be routed to it.
- `-f <cap>, --frontend <cap>`  
Set the frontend for the current multiplexer. Output for the multiplexer is then sent to the capability with the given name `<cap>`. The server connected to the capability needs to understand the [L4::Vcon](#) protocol.
- `-V <cap>, --virtio-device-frontend <cap>`  
Set a virtio-console frontend for the current multiplexer. This behaves identical to the `--frontend` option except that this frontend implements a virtio-console device that –for example– can be connected to a virtio proxy in uvmm.

Example lua:

```
-- use 'cons_svr' to create client sessions
local cons_svr = loader:new_channel()
-- connect 'virtio_device' with a virtio driver (e.g. Uvmm)
local virtio_device = loader:new_channel()
loader:start(
{
  caps = {
    virtio = virtio_device,
    cons = cons_svr:svr(),
  },
  log = {"cons", "blue"},
}, "cons -m guests -V virtio")
```

- `-k, --keep`  
Keep the console buffer when a client disconnects.
- `-l, --no-line-buffering`  
By default, merge the client output to entire lines. If the client writes characters without a final newline, the following client output is merged with the current line content. Specifying this switch disables the line buffered mode by default.
- `--line-buffering-ms <timeout>`  
Timeout in milliseconds before buffered client output is written even without a newline. Default value is 50.
- `-m <prompt name>, --mux <prompt name>`  
Add a new multiplexer named `<prompt name>`. This is necessary if output should be sent to different frontends. This option must be used in conjunction with the `-f` frontend option
- `-n, --defaultname`  
Default name for the multiplexer prompt. Default: `cons`.
- `-t, --timestamp`  
Prefix the output with timestamps.

## Connecting a client

```
create(backend_type, ["client_name"], ["color"], ["option"] [, "option"] ...)
```

- `backend_type`

The type of backend that should be created for the client. The type is a positive integer and currently the following types are supported:

- `L4.Proto.Log: L4::Vcon` client
- `1`: Virtio console client

`cons` accepts the following per-client options:

- `bufsz=n`

Use a buffer of `n` bytes for this client, deviating from the default buffer size.

- `keep / no-keep`

The console buffer is kept / thrown away when the client disconnects.

- `key=<key>`

Assign `<key>` as keyboard shortcut to this client.

- `line-buffering / no-linux-buffering`

Line buffering is enabled / disabled for this client.

- `show / hide`

Output from this client is initially shown / hidden.

- `timestamp / no-timestamp`

Do / do not prefix the output of this client with timestamps.



## Chapter 5

# uvmm\_dtg The device tree generator for Uvmm

A virtual machine in Uvmm is configured with a device tree that contains information about the VMs resources, memory layout, virtual CPUs and peripheral devices.

Uvmm\_dtg is a tool to generate such a device tree at runtime according to its command line.

### Capabilities

- dt

The dataspace that the device tree is put into.

### Command Line Options

`<file | -->`

-- prints to stdout. On [L4Re](#), the string given as `<file>` is interpreted as a named capability which needs to be backed by a sufficiently large Dataspace. On Linux, a file with the given name is created. In both cases, uvmm\_dtg will output into the named file.

String value.

- -h, --help

Show help.

Flag. True if provided.

- --arch `<target architecture>`

Select the target architecture.

Possible values for `<target architecture>` are x86, x86\_64, arm32, arm64, mips32, mips64

- --format `<format>`

Select the output format.

Possible values for `<format>` are

- txt: The device tree will be printed as plain text (dts).
- bin: The device tree will be output as binary (dtb).
- --mem-base <membase>  
Configure the start of the memory distribution. membase can be defined in both decimal and hex notations. uvmm\_dtg rounds the given base up to the platforms page size.  
This value can be overridden by memory devices with fixed addresses.  
Numerical value.
- --device <devicename:[Option1,Option2=value,Option3=value,...]>  
This configures a device.  
To get a list of supported devices, use --device help.  
To get help for a specific device, use --device devicename:help.  
String value.

## Examples

### Usage in L4Re

Example lua script for Ned:

```
-- Create DS holding device tree
local dt = L4.Env.user_factory:create(L4.Proto.Dataspace, 4 * 1024):m("rw");

-- Start the generator
L4.default_loader:start(
{
  caps = { dt = dt },
}, "rom/uvmm_dtg dt"):wait();

-- Start uvmm
vmm.start_vm
{
  ...
  ext_caps = { dt = dt },
  fdt = "dt",
  ...
}
```

Please notice the :wait() when starting uvmm\_dtg. This makes Ned pause until uvmm\_dtg has exited and put the device tree into the dataspace such that Uvmm can commence.



## Chapter 6

# Bootstrap, the L4 kernel bootstrapper

### Bootstrap Command Line Options

`bootstrap` and the kernel can be configured through command line switches. `bootstrap` is responsible for parsing both command lines: `bootstrap` options are the ones directly given to `bootstrap`, whereas kernel options are those directly given to the kernel, respectively.

When using Multiboot boot, the first module directly after `bootstrap` is considered the kernel: An example using GRUB2 might look like this:

```
multiboot /path/to/bootstrap bootstrap -bs-boolean-opt -bs-opt-with-argument=foo
module /path/to/fiasco fiasco -kernel-opt-with-argument=bar -kernel-boolean-opt
```

#### Note

The exact way to provide the command line to `bootstrap` is platform-dependent. On platforms supporting booting via Multiboot Specification the command line can be specified in the boot configuration (currently x86/amd64 only, e.g. using GRUB) whereas other platforms need the command line to be compiled into the `bootstrap` binary.

Platforms utilising flattened device trees usually also allow specifying a command line through the DT. This mechanism is **not** currently supported in `bootstrap`!

#### Note

`bootstrap` will ignore options it does not understand. For most cases, this also holds true if an option's arguments cannot be understood.

## bootstrap options

Command line options directly understood by `bootstrap` itself are as follows (passed via `bootstrap` command line):

- `-comirq=<irqno>` (x86/amd64 only)

If serial logging is enabled (default on), `<irqno>` defines which IRQ to use for serial port communication. This option is ignored if `-noserial` is also specified (see below).

- `-comport=<portspec>` (x86/amd64 only)

If serial logging is enabled (default on), `<portspec>` defines which serial port to use, being one of:

- `<number>`  
Use legacy port `<number>`, e.g. use `-comport=1` for the port commonly known as *COM1*, or
- `pci:<card>:<port>`  
Use serial port number `<port>` at PCI card number `<card>`, e.g. use `-comport=pci:0:1` for the second port on the first PCI card.
- `pci:probe`  
Use this to have `bootstrap` autodiscover all PCI serial lines. On each discovered line a message will be displayed, telling the correct `<portspec>` to be given to use the respective line.

### Note

`bootstrap` does not support specifying the serial port's baudrate and always uses 115200 bps.

- `-noserial`

Disable serial logging.

- `-wait`

Wait for key press at early startup.

### Note

This is not to be confused with the kernel's `-wait` option, see below.

- `-maxmem=<mbytes>`

Limit the available memory to at most `<mbytes>` MiB.

- `-mem=<size>@<offset>`

Add a region of memory of `<size>` at `<offset>` to the system's memory map. Both `<size>` and `<offset>` may be suffixed by either G, M, or K/k to denote GiB, MiB, or KiB, respectively.

This option may be specified multiple times. If the option is not given, a platform-specific method for determining the memory layout will be used, if available.

- `-presetmem=<intval>`

Initialise memory regions with `<intval>` before starting the kernel.

- `-modaddr=<paddr>`

Relocate modules to the physical address `<paddr>`. Use this when utilising a version of GRUB that lacks support for the `modaddr` command.

## Kernel Options

Command line options for the kernel (passed on kernel command line, i.e. to first module) `bootstrap` understands are as follows.

### Note

Availability of individual options might depend on used platform and/or actual kernel configuration.

- `-wait`  
Enter debugger directly after startup, prior to executing any task.
- `-serial_esc`  
Enable entering the debugger over serial line by pressing `Esc`. This option also activates `-serial_input`.
- `-serial_input`  
Allow the kernel to read from the serial line either triggered by the UART receive interrupt or (if that is not possible) by polling the UART receive register from the kernel timer interrupt handler. This is required for Vlog clients to receive input.
- `-noserial`  
Disable serial logging.

### Note

If this is given as kernel command line argument, it does not affect `bootstrap` but only the kernel.

- `-noscreen`  
Disable VGA console.
- `-esc`  
Enable entering the debugger by pressing `Esc` on attached keyboard.
- `-nojdb`  
Disable the kernel debugger.
- `-nohlt`  
Enable quirk for broken HLT instruction.
- `-apic`  
Use Advanced Programmable Interrupt Controller (APIC) if available and known to be well-behaving.
- `-loadcnt`  
Use load counter for performance counting.
- `-watchdog`  
Enable watchdog timer.
- `-irq0`  
Allow IRQ 0 to be used by userland. This enables some sanity checks to ensure IRQ 0 is not used by the kernel, e.g. for profiling or scheduling purposes. This only has an effect on x86.
- `-nosfn`  
Disable SFN (special fully nested) mode of interrupt controller. This only has an effect on x86 with PIC8259 interrupt controller.
- `-jdb_never_stop`  
Prevent system from stopping to enter JDB. This only has an effect on x86.

- `-kmemsize=<KB>`  
Reserve `<KB>` KiB of memory for the kernel.
- `-tbuf_entries=<number>`  
Specify the `<number>` of trace buffer entries.
- `-out_buf=<length>`  
Specify length of console buffer to be `<length>` bytes.
- `-jdb_cmd=<ctrlseq>`  
Execute JDB command sequence `<ctrlseq>` right after start-up. If `-wait` is also given, `<ctrlseq>` is executed right before entering JDB.

## Module options

Bootstrap supports module attributes for `sigma0` and the `roottask`. They need to be specified in `modules.list`, e.g.:

```
sigma0[attr:nodes=4-7] ...
```

Attributes are not supported when using multi-boot on platforms that support it. The following attributes are supported:

- `nodes`

This is a colon separated list of AMP node ranges. A range can also be a single number. Examples:

- `nodes=1` – Only node 1
- `nodes=1-3` – Nodes 1 to 3 (inclusive)
- `nodes=0:2-3` – Nodes 0, 2 and 3

If not present, the `sigma0/roottask` module is applicable to all AMP nodes.

- `reloc`

Normally the `sigma0` or `roottask` images are loaded at the preferred load address if the RAM is available at the desired location. If this is not possible, they will be relocated to some free RAM region. Setting the "reloc" module attribute to a non-empty string will always request the dynamic relocation.

This attribute can be used on no-MMU systems to maximize the size of contiguous free RAM regions.

# Chapter 7

## Deprecated List

Global `L4::Rcv_endpoint::bind_thread (Ipc::Cap< Thread > t, I4_umword_t label)`

Use `bind_snd_destination()` instead.

Global `L4_CAP_SIZE`

Superseded by `L4_CAP_OFFSET`.

Global `I4_kip_clock_lw (I4_kernel_info_t const *kip) L4_NOTHROW`

Use `I4_kip_clock()` instead.

Global `L4Re::Util::Registry_server< LOOP_HOOKS >::Registry_server (I4_utcb_t *, L4::Cap< L4::Thread > server, L4::Cap< L4::Factory > factory)`

Note that this variant of the constructor is deprecated, please do not supply the UTCB pointer, it's not used.

Global `I4util_kip_for_each_feature (s)`

Use `I4_kip_for_each_feature()`.

Global `I4util_kip_kernel_has_feature (I4_kernel_info_t const *k, char const *str)`

Use `I4_kip_kernel_has_feature()`.

Global `I4util_micros2I4to (I4_uint64_t us) L4_NOTHROW`

Use `I4_timeout_from_us()`.

Global `start_virtio_switch (ports, prio, cpus, switch_type, ext_caps)`

This function exists for backwards compatibility reasons and calls `start_virtio_switch_tbl` with an appropriate `options` table



# Chapter 8

## Topic Index

### 8.1 Topics

Here is a list of all topics with brief descriptions:

Base API	149
Basic Macros	152
Fiasco extensions	157
Kernel Debugger	161
Kernel Information Dump	169
Kernel Tracing	170
Flexpages	173
C++ IPC Interface Definition	191
Internal Helpers	192
Cache Consistency	192
Memory related	196
Error codes	205
Object Invocation	207
Message Items	225
Attributes and additional permissions for object send items	231
Timeouts	232
Error Handling	241
Realtime API	247
Message Tag	247
Virtual Registers (UTCBS)	260
Message Registers (MRs)	265
Exception registers	266
Buffer Registers (BRs)	269
Thread Control Registers (TCRs)	270
ARM Virtual Registers (UTCBS)	271
ARM64 Virtual Registers (UTCBS)	271
AMD64 Virtual Registers (UTCBS)	272
x86 Virtual Registers (UTCBS)	272
Kernel Objects	273
IPC-Gate API	275
DMA space	280
L4 kernel object type information	280
Factory	282
Virtual Machines	293

VM API for SVM	293
VM API for VMX	294
VM API for TZ	314
Interrupt controller	314
IRQs	331
Platform Control C API	346
Scheduler	352
Kernel-provided semaphore	360
Task	362
Thread	374
Thread control	397
vCPU API	403
Thread groups	408
Virtual Console	410
Kernel Interface Page	425
Memory descriptors (C version)	432
Capabilities	437
Memory Operations	441
Integer Types	444
EDID parsing functionality	446
IO interface	450
IPC Helpers	458
IRQ handling library	459
Interface using direct functionality.	460
Interface using direct functionality.	465
Interface for asynchronous ISR handlers.	467
Interface for asynchronous ISR handlers with a given IRQ capability.	469
L4 IPC Opcodes	470
L4 VIRTIO Interface	475
L4 VIRTIO Transport Layer	475
L4 VIRTIO Block Device	484
L4 VIRTIO Input Device	486
L4 VIRTIO Network Device	486
L4 Vbus functions	487
L4vbus GPIO functions	497
L4vbus PCI functions	508
L4vbus power management functions	514
L4Re C Interface	516
L4Re Util C Interface	518
Dataspace interface	518
Debug interface	524
DMA Space Interface	525
Event interface	529
Log interface	532
Memory allocator	535
Namespace interface	540
Parent interface	544
Region map interface	544
Capability allocator	559
Kumem allocator utility	560
Video API	561
Initial Environment	569
L4Re C++ Interface	574
L4Re Util C++ Interface	576
L4Re Capability API	577
Kumem utilities	579



Console API . . . . .	581
Debugging API . . . . .	581
L4Re ELF Auxiliary Information . . . . .	582
Event API . . . . .	584
Auxiliary data . . . . .	585
Logging interface . . . . .	586
Name-space API . . . . .	586
Parent API . . . . .	587
L4Re Protocol identifiers . . . . .	588
Region map API . . . . .	589
Video API . . . . .	590
C++ Exceptions . . . . .	591
Vbus API . . . . .	592
L4SHM-based ring buffer implementation . . . . .	593
Sender . . . . .	594
Receiver . . . . .	594
Internal . . . . .	594
Shared Memory Library . . . . .	596
Chunks . . . . .	602
Producer . . . . .	607
Consumer . . . . .	610
Signals . . . . .	615
Producer . . . . .	618
Consumer . . . . .	619
Sigma0 API . . . . .	623
Internal constants . . . . .	628
Small C++ Template Library . . . . .	629
The L4Re IPC Framework . . . . .	633
Server-Side IPC framework . . . . .	633
Utility Functions . . . . .	635
CPU related functions . . . . .	642
IA32 Port I/O API . . . . .	645
Timestamp Counter . . . . .	651
Atomic Instructions . . . . .	658
Internal functions . . . . .	676
Bit Manipulation . . . . .	676
ELF binary format . . . . .	683
Kernel Interface Page API . . . . .	708
Comfortable Command Line Parsing . . . . .	710
Random number support . . . . .	712
Low-Level Thread Functions . . . . .	713
Virtio Net Switch . . . . .	713
vCPU Support Library . . . . .	714
Extended vCPU support . . . . .	721



## Chapter 9

# Namespace Index

### 9.1 Namespace List

Here is a list of all documented namespaces with brief descriptions:

<a href="#">cxx</a>	Our C++ library . . . . .	723
<a href="#">cxx::Bits</a>	Internal helpers for the cxx package . . . . .	729
<a href="#">Enum_bitops</a>	Mechanism to opt-in for enum bitwise operators . . . . .	730
<a href="#">Enum_bitops_impl</a>	Bitwise operators on enumeration types . . . . .	730
<a href="#">L4</a>		
	<a href="#">L4</a> low-level kernel interface . . . . .	731
<a href="#">L4::lpc</a>	IPC related functionality . . . . .	742
<a href="#">L4::lpc::Msg</a>	IPC Message related functionality . . . . .	750
<a href="#">L4::lpc_svr</a>	Helper classes for <a href="#">L4::Server</a> instantiation . . . . .	757
<a href="#">L4::Typeid</a>	Definition of interface data-type helpers . . . . .	758
<a href="#">L4::Types</a>		
	<a href="#">L4</a> basic type helpers for C++ . . . . .	758
<a href="#">L4Re</a>		
	<a href="#">L4Re</a> C++ Interfaces . . . . .	760
<a href="#">L4Re::Util</a>	Documentation of the <a href="#">L4</a> Runtime Environment utility functionality in C++ . . . . .	775
<a href="#">L4Re::Vfs</a>	Virtual file system for interfaces in POSIX libc . . . . .	782
<a href="#">L4vbus</a>	C++ interface of the <a href="#">Vbus</a> API. . . . .	783
<a href="#">L4virtio</a>	L4-VIRTIO Transport C++ API . . . . .	784



## Chapter 10

# Hierarchical Index

### 10.1 Class Hierarchy

This inheritance list is sorted roughly, but not completely, alphabetically:

cxx::arith::Ld< V > . . . . .	787
cxx::Base_slab< Obj_size, Slab_size, Max_free, Alloc > . . . . .	808
cxx::Base_slab< sizeof(Type), L4_PAGESIZE, 2, New_allocator > . . . . .	808
cxx::Slab< Type, Slab_size, Max_free, Alloc > . . . . .	937
cxx::Base_slab_static< Obj_size, Slab_size, Max_free, Alloc > . . . . .	813
cxx::Base_slab_static< sizeof(Type), L4_PAGESIZE, 2, New_allocator > . . . . .	813
cxx::Slab_static< Type, Slab_size, Max_free, Alloc > . . . . .	942
cxx::Bitfield< T, LSB, MSB > . . . . .	818
cxx::Bitfield< T, LSB, MSB >Value_base< TT > . . . . .	827
cxx::Bitfield< T, LSB, MSB >Value< Base_type & > . . . . .	826
cxx::Bitfield< T, LSB, MSB >Value< Base_type volatile & > . . . . .	826
cxx::Bitfield< T, LSB, MSB >Value< Base_type const > . . . . .	826
cxx::Bitfield< T, LSB, MSB >Value_unshifted< Base_type & > . . . . .	828
cxx::Bitfield< T, LSB, MSB >Value_unshifted< Base_type volatile & > . . . . .	828
cxx::Bitfield< T, LSB, MSB >Value_unshifted< Base_type const > . . . . .	828
cxx::Bitfield< T, LSB, MSB >Value< TT > . . . . .	826
cxx::Bitfield< T, LSB, MSB >Value_unshifted< TT > . . . . .	828
cxx::Bitmap_base . . . . .	834
cxx::Bitmap< BITS > . . . . .	830
cxx::Bitmap_base::Bit . . . . .	847
cxx::Bitmap_base::Char< BITS > . . . . .	847
cxx::Bitmap_base::Word< BITS > . . . . .	848
cxx::Bits::Avl_map_get_key< KEY_TYPE > . . . . .	849
cxx::Bits::Avl_set_get_key< KEY_TYPE > . . . . .	850
cxx::Bits::Avl_set_iter< Node, Key, Node_op > . . . . .	850
cxx::Bits::Avl_set_iter< _Node, Const_item_type, Fwd > . . . . .	850
cxx::Bits::Avl_set_iter< _Node, Const_item_type, Rev > . . . . .	850
cxx::Bits::Avl_set_iter< _Node, Item_type, Fwd > . . . . .	850
cxx::Bits::Avl_set_iter< _Node, Item_type, Rev > . . . . .	850
cxx::Bits::Avl_set_iter< Node, Non_const_key, Node_op > . . . . .	850
cxx::Bits::Base_avl_set< ITEM_TYPE, COMPARE, ALLOC, GET_KEY > . . . . .	854
cxx::Avl_map< Region, Hdlr, cxx::Lt_functor, Alloc > . . . . .	788
cxx::Bits::Base_avl_set< ITEM_TYPE, COMPARE, ALLOC, GET_KEY >Node . . . . .	864

cxx::Bits::Base_avl_set< ITEM_TYPE, Lt_funcutor< ITEM_TYPE >, New_allocator, Bits::Avl_set_get_↵ key< ITEM_TYPE > > . . . . .	854
cxx::Avl_set< ITEM_TYPE, COMPARE, ALLOC > . . . . .	794
cxx::Bits::Base_avl_set< Pair< KEY_TYPE, DATA_TYPE >, Lt_funcutor< KEY_TYPE >, New_allocator, Bits::Avl_map_get_key< KEY_TYPE > > . . . . .	854
cxx::Avl_map< KEY_TYPE, DATA_TYPE, COMPARE, ALLOC > . . . . .	788
cxx::Bits::Basic_list< POLICY > . . . . .	866
cxx::H_list< Timeout > . . . . .	892
cxx::H_list< Observer > . . . . .	892
cxx::H_list< cxx::Base_slab::Slab_i > . . . . .	892
cxx::S_list< T, POLICY > . . . . .	934
cxx::H_list< T, POLICY > . . . . .	892
cxx::Bits::Basic_list< Bits::Basic_list_policy< T, H_list_item_t< T > > > . . . . .	866
cxx::H_list< T, Bits::Basic_list_policy< T, H_list_item_t< T > > > . . . . .	892
cxx::H_list_t< T > . . . . .	902
cxx::Bits::Basic_list< Bits::Basic_list_policy< T, S_list_item > > . . . . .	866
cxx::S_list< T, Bits::Basic_list_policy< T, S_list_item > > . . . . .	934
cxx::S_list< T, POLICY > . . . . .	934
cxx::Bits::Basic_list< Bits::Basic_list_policy< Weak_ref_base, H_list_item_t< Weak_ref_base > > > . . . . .	866
cxx::H_list< Weak_ref_base, Bits::Basic_list_policy< Weak_ref_base, H_list_item_t< Weak_ref_↵ base > > > . . . . .	892
cxx::H_list_t< Weak_ref_base > . . . . .	902
cxx::Weak_ref_base::List . . . . .	960
cxx::Bits::Bst< Node, Get_key, Compare > . . . . .	869
cxx::Avl_tree< Entry, Names_get_key > . . . . .	798
cxx::Avl_tree< _Node, GET_KEY, COMPARE > . . . . .	798
cxx::Avl_tree< Node, Get_key, Compare > . . . . .	798
cxx::Bits::Bst< _Node, Bits::Avl_map_get_key< KEY_TYPE >, Lt_funcutor< KEY_TYPE > > . . . . .	869
cxx::Avl_tree< _Node, Bits::Avl_map_get_key< KEY_TYPE >, Lt_funcutor< KEY_TYPE > > . . . . .	798
cxx::Bits::Bst< _Node, Bits::Avl_set_get_key< ITEM_TYPE >, Lt_funcutor< ITEM_TYPE > > . . . . .	869
cxx::Avl_tree< _Node, Bits::Avl_set_get_key< ITEM_TYPE >, Lt_funcutor< ITEM_TYPE > > . . . . .	798
cxx::Bits::Bst_node . . . . .	882
cxx::Avl_tree_node . . . . .	806
cxx::Bits::Direction . . . . .	884
cxx::Bits::Smart_ptr_list< ITEM > . . . . .	886
cxx::Bits::Smart_ptr_list_item< T, STORE_T > . . . . .	889
cxx::Bits::Smart_ptr_list_item< T, cxx::Ref_ptr< T > > . . . . .	889
cxx::Ref_obj_list_item< T > . . . . .	927
cxx::Elide_dtor< T > . . . . .	891
cxx::H_list_item_t< ELEM_TYPE > . . . . .	899
cxx::H_list_item_t< void > . . . . .	899
L4::lpc_svr::Timeout . . . . .	1240
cxx::H_list_item_t< Weak_ref_base > . . . . .	899
cxx::Weak_ref_base . . . . .	957
cxx::Weak_ref< T > . . . . .	955
cxx::List< D, Alloc > . . . . .	906
cxx::List< D, Alloc >Iter . . . . .	908
cxx::List_alloc . . . . .	909
cxx::List_item . . . . .	913
cxx::List_item::Iter . . . . .	916
cxx::List_item::T_iter< E > . . . . .	918
cxx::List_item::T_iter< T, Poly > . . . . .	918
cxx::Lt_funcutor< Obj > . . . . .	920
cxx::New_allocator< _Type > . . . . .	920

cxx::Nothrow	922
cxx::Pair< First, Second >	922
cxx::Pair_first_compare< Cmp, Typ >	925
cxx::Ref_ptr< T, CNT >	929
cxx::Ref_ptr< L4Re::Vfs::File >	929
cxx::Ref_ptr< Mount_tree >	929
cxx::Ref_ptr< T, CNT >	929
cxx::static_vector< T, IDX >	946
cxx::String	947
L4Re::Util::Names::Name	1809
Elf32_Auxv	964
Elf32_Dyn	965
Elf32_Ehdr	966
Elf32_Phdr	969
Elf32_Rel	970
Elf32_Rela	971
Elf32_Shdr	972
Elf32_Sym	974
Elf64_Auxv	975
Elf64_Dyn	976
Elf64_Ehdr	977
Elf64_Phdr	979
Elf64_Rel	981
Elf64_Rela	981
Elf64_Shdr	982
Elf64_Sym	984
L4::Alloc_list	991
L4::Basic_registry	996
L4Re::Util::Object_registry	1817
L4::Cap_base	1008
L4::Cap< A >	1002
L4::Cap< L4Re::Namespace >	1002
L4::Cap< L4Re::Dataspace >	1002
L4::Cap< L4::Vcon >	1002
L4::Cap< L4::Semaphore >	1002
L4::Cap< L4Re::Rm >	1002
L4::Cap< L4::Irq >	1002
L4::Cap< L4::Thread >	1002
L4::Cap< L4::Factory >	1002
L4::Cap< L4Re::Video::Goos >	1002
L4::Cap< L4vbus::Vbus >	1002
L4::Cap< L4virtio::Device >	1002
L4::Smart_cap< T, Smart_count_cap< L4_FP_ALL_SPACES > >	1386
L4::Smart_cap< T, Smart_count_cap< L4_FP_DELETE_OBJ > >	1386
L4::Cap< T >	1002
L4::Smart_cap< T, SMART >	1386
L4::Epiface	1041
L4::Epiface_t0< IFACE, L4::Epiface >	1049
L4::Epiface_t< Derived, IFACE, BASE, bool >	1046
L4::Epiface_t0< void, Epiface >	1049
L4::Irqep_t< Irq_object >	1269
L4::Irqep_t< Host_irq >	1269
L4virtio::Svr::Virtio_gpio< Request_handler, Epiface >Host_irq	2214
L4virtio::Svr::Virtio_i2c< Request_handler, Epiface >Host_irq	2226
L4virtio::Svr::Virtio_rng< Rnd_state, Epiface >Host_irq	2237
L4virtio::Svr::Virtio_spi< Spi_request_handler, Epiface >Host_irq	2248
L4::Irqep_t< Del_cap_irq >	1269

L4::Irqep_t< Kick_irq > . . . . .	1269
L4::Irqep_t< Derived, BASE, bool > . . . . .	1269
L4::Epiface_t0< L4::Kobject, L4::Epiface > . . . . .	1049
L4::Epiface_t< Null_handler, L4::Kobject > . . . . .	1046
L4::Epiface_t0< L4virtio::Device, L4::Epiface > . . . . .	1049
L4::Epiface_t< Block_dev< Ds_data >, L4virtio::Device > . . . . .	1046
L4::Epiface_t< Virtio_gpio< Request_handler, L4virtio::Device >, L4virtio::Device > . . . . .	1046
L4virtio::Svr::Virtio_gpio< Request_handler, Epiface > . . . . .	2210
L4::Epiface_t< Virtio_i2c< Request_handler, L4virtio::Device >, L4virtio::Device > . . . . .	1046
L4virtio::Svr::Virtio_i2c< Request_handler, Epiface > . . . . .	2222
L4::Epiface_t< Virtio_rng< Rnd_state >, L4virtio::Device > . . . . .	1046
L4virtio::Svr::Virtio_rng< Rnd_state, Epiface > . . . . .	2233
L4::Epiface_t< Virtio_spi< Spi_request_handler, L4virtio::Device >, L4virtio::Device > . . . . .	1046
L4virtio::Svr::Virtio_spi< Spi_request_handler, Epiface > . . . . .	2243
L4::Epiface_t< Virtio_net, L4virtio::Device > . . . . .	1046
Virtio_net . . . . .	2345
L4virtio_port . . . . .	2306
L4::Epiface_t0< L4::Factory, L4::Epiface > . . . . .	1049
L4::Epiface_t< Switch_factory, L4::Factory > . . . . .	1046
Switch_factory . . . . .	2341
L4::Epiface_t0< Virtio_net_switch::Statistics_if, L4::Epiface > . . . . .	1049
L4::Epiface_t< Stats_reader, Virtio_net_switch::Statistics_if > . . . . .	1046
L4::Epiface_t0< RPC_IFACE, BASE > . . . . .	1049
L4::Server_object . . . . .	1372
L4::Server_object_t< Kobject > . . . . .	1377
L4::Irq_handler_object . . . . .	1265
L4::Server_object_t< IFACE, L4::Server_object > . . . . .	1377
L4::Server_object_x< Derived, IFACE, BASE > . . . . .	1382
L4::Server_object_t< IFACE, BASE > . . . . .	1377
L4::Server_object_x< Derived, IFACE, BASE > . . . . .	1382
L4::Epiface_t0< IFACE, BASE > . . . . .	1049
L4::Epiface_t0< void, BASE > . . . . .	1049
L4::Exception_tracer . . . . .	1054
L4::Base_exception . . . . .	994
L4::Invalid_capability . . . . .	1087
L4::Runtime_error . . . . .	1348
L4::Bounds_error . . . . .	999
L4::Com_error . . . . .	1021
L4::Element_already_exists . . . . .	1034
L4::Element_not_found . . . . .	1038
L4::Out_of_memory . . . . .	1315
L4::Unknown_error . . . . .	1510
L4::Factory::Lstr . . . . .	1066
L4::Factory::Nil . . . . .	1068
L4::Factory::S . . . . .	1068
L4::IOModifier . . . . .	1098
L4::lpc::Array_in_buf< ELEM_TYPE, LEN_TYPE, MAX > . . . . .	1101
L4::lpc::Array_ref< ELEM_TYPE, LEN_TYPE > . . . . .	1104
L4::lpc::Array_ref< A, LEN > . . . . .	1104
L4::lpc::Array< A, LEN > . . . . .	1098
L4::lpc::Array< A, LEN > & . . . . .	1098
L4::lpc::Array_ref< char const, unsigned long > . . . . .	1104
L4::lpc::Array< char const, unsigned long > . . . . .	1098
L4::lpc::Array_ref< ELEM_TYPE, Array_len_default > . . . . .	1104
L4::lpc::Array< ELEM_TYPE, LEN_TYPE > . . . . .	1098



L4::lpc::Array_ref< X, LEN_TYPE > . . . . .	1104
L4::lpc::Array< X, LEN_TYPE > . . . . .	1098
L4::lpc::As_value< T > . . . . .	1105
L4::lpc::Call . . . . .	1106
L4::lpc::Call_t< RIGHTS > . . . . .	1107
L4::lpc::Call_zero_send_timeout . . . . .	1108
L4::lpc::Cap< T > . . . . .	1109
L4::lpc::Gen_fpage . . . . .	1113
L4::lpc::Rcv_fpage . . . . .	1172
L4::lpc::Snd_fpage . . . . .	1183
L4::lpc::In_out< T > . . . . .	1116
L4::lpc::Istream . . . . .	1127
L4::lpc::Iostream . . . . .	1117
L4::lpc::Msg::Cnt_val_ops< MTYPE, DIR, CLASS > . . . . .	1138
L4::lpc::Msg::Cnt_val_ops< Detail::_Plain< T >type, DIR, CLASS > . . . . .	1138
L4::lpc::Msg::Cnt_val_ops< Detail::_Plain< T >type, typename Direction< T >type, typename Class< typename Detail::_Plain< T >type >type > . . . . .	1138
L4::lpc::Msg::Cnt_val_ops< Detail::_Plain< typename _Elem< A * >arg_type >type, typename Direction< A * >type, typename Class< typename Detail::_Plain< A * >type >type > . . . . .	1138
L4::lpc::Msg::Cnt_val_ops< Detail::_Plain< typename _Elem< A const * >arg_type >type, typename Direction< A const * >type, typename Class< typename Detail::_Plain< A const * >type >type > . . . . .	1138
L4::lpc::Msg::Cnt_val_ops< Detail::_Plain< typename _Elem< Array< A, LEN > & >arg_type >type, typename Direction< Array< A, LEN > & >type, typename Class< typename Detail::_Plain< Array< A, LEN > & >type >type > . . . . .	1138
L4::lpc::Msg::Cls_buffer . . . . .	1139
L4::lpc::Msg::Do_rcv_buffers . . . . .	1150
L4::lpc::Msg::Cls_data . . . . .	1141
L4::lpc::Msg::Do_in_data . . . . .	1145
L4::lpc::Msg::Do_out_data . . . . .	1147
L4::lpc::Msg::Cls_item . . . . .	1142
L4::lpc::Msg::Do_in_items . . . . .	1146
L4::lpc::Msg::Do_out_items . . . . .	1148
L4::lpc::Msg::Dir_in . . . . .	1143
L4::lpc::Msg::Do_in_data . . . . .	1145
L4::lpc::Msg::Do_in_items . . . . .	1146
L4::lpc::Msg::Do_rcv_buffers . . . . .	1150
L4::lpc::Msg::Dir_out . . . . .	1144
L4::lpc::Msg::Do_out_data . . . . .	1147
L4::lpc::Msg::Do_out_items . . . . .	1148
L4::lpc::Msg::Elem< Array< A, LEN > & > . . . . .	1151
L4::lpc::Msg::Elem< Array< A, LEN > > . . . . .	1152
L4::lpc::Msg::Elem< Array_ref< A, LEN > & > . . . . .	1153
L4::lpc::Msg::Svr_arg_pack< IPC_TYPE > . . . . .	1158
L4::lpc::Msg::Svr_val_ops< MTYPE, DIR, CLASS > . . . . .	1158
L4::lpc::Msg::Svr_val_ops< L4::lpc::Snd_fpage, Dir_in, CLASS > . . . . .	1158
L4::lpc::Msg_ptr< T > . . . . .	1162
L4::lpc::Opt< T > . . . . .	1163
L4::lpc::Ostream . . . . .	1165
L4::lpc::Iostream . . . . .	1117
L4::lpc::Out< T > . . . . .	1171
L4::lpc::Ret_array< T > . . . . .	1179
L4::lpc::Send_only . . . . .	1180
L4::lpc::Small_buf . . . . .	1181
L4::lpc::Str_cp_in< T > . . . . .	1193

L4::lpc::Varg	1194
L4::lpc::Varg_list_ref	1203
L4::lpc::Varg_list< MAX >	1200
L4::lpc::Varg_list_ref::iterator	1205
L4::lpc_svr::Compound_reply	1216
L4::lpc_svr::Default_loop_hooks	1220
L4::Server< L4::lpc_svr::Default_loop_hooks >	1366
L4Re::Util::Registry_server< LOOP_HOOKS >	1827
L4::Server< LOOP_HOOKS >	1366
L4Re::Util::Br_manager_hooks	1772
L4::lpc_svr::Default_setup_wait	1223
L4::lpc_svr::Default_timeout	1224
L4::lpc_svr::Default_loop_hooks	1220
L4Re::Util::Br_manager_hooks	1772
L4::lpc_svr::Direct_dispatch< R >	1226
L4::lpc_svr::Dbg_dispatch< R, Exc, Printer >	1218
L4::lpc_svr::Exc_dispatch< R, Exc >	1230
L4::lpc_svr::Direct_dispatch< R * >	1228
L4::lpc_svr::Ignore_errors	1232
L4::lpc_svr::Default_loop_hooks	1220
L4Re::Util::Br_manager_hooks	1772
L4Re::Util::Br_manager_timeout_hooks	1774
L4::lpc_svr::Server_iface	1233
L4::lpc_svr::Timeout_queue_hooks< Br_manager_timeout_hooks, Br_manager >	1247
L4Re::Util::Br_manager_timeout_hooks	1774
L4::lpc_svr::Br_manager_no_buffers	1212
L4::lpc_svr::Default_loop_hooks	1220
L4::lpc_svr::Timeout_queue_hooks< HOOKS, BR_MAN >	1247
L4::lpc_svr::Timeout_queue_hooks< HOOKS, BR_MAN >	1247
L4Re::Util::Br_manager	1766
L4Re::Util::Br_manager_hooks	1772
L4::lpc_svr::Timeout_queue	1244
L4::Kip::Mem_desc	1273
L4::Kobject	1284
L4::Kobject_t< Arm_smccc, L4::Kobject, PROTO, Type_info::Demand_t<> >	1296
L4::Kobject_t< Debugger, Kobject, L4_PROTO_DEBUGGER >	1296
L4::Debugger	1024
L4::Kobject_t< Exception, L4::Kobject, PROTO, Type_info::Demand_t<> >	1296
L4::Kobject_t< Factory, Kobject, L4_PROTO_FACTORY >	1296
L4::Factory	1055
L4::Kobject_t< Mem_alloc, L4::Factory, L4RE_PROTO_MEM_ALLOC >	1296
L4Re::Mem_alloc	1681
L4::Kobject_t< Io_pager, L4::Kobject, PROTO, Type_info::Demand_t<> >	1296
L4::Kobject_t< Irq_eoi, L4::Kobject, PROTO, Type_info::Demand_t<> >	1296
L4::Kobject_t< Derived, L4::Kobject, L4::PROTO_ANY, Type_info::Demand_t<> >	1296
L4::Kobject_t< Meta, Kobject, L4_PROTO_META >	1296
L4::Meta	1309
L4::Kobject_t< Platform_control, Kobject, L4_PROTO_PLATFORM_CTL >	1296
L4::Platform_control	1322
L4::Kobject_t< Rcv_endpoint, Kobject, L4_PROTO_KOBJECT, Type_info::Demand_t< 1 > >	1296
L4::Rcv_endpoint	1337
L4::Kobject_2t< Irq, Triggerable, Rcv_endpoint, L4_PROTO_IRQ_SENDER >	1288
L4::Irq	1252
L4::Kobject_t< lpc_gate, Rcv_endpoint, L4_PROTO_KOBJECT, Type_info::Demand_t< 1 > >	1296
L4::lpc_gate	1207

L4::Kobject_t< Snd_destination, Kobject, L4_PROTO_KOBJECT > . . . . .	1296
L4::Kobject_t< Task, Kobject, L4_PROTO_TASK, Type_info::Demand_t< 2 > > . . . . .	1296
L4::Task . . . . .	1391
L4::Kobject_t< Vm, Task, L4_PROTO_VM > . . . . .	1296
L4::Vm . . . . .	1523
L4::Kobject_t< Vcpu_context, Kobject, L4_PROTO_VCPU_CONTEXT > . . . . .	1296
L4::Kobject_t< Dataspace, L4::Kobject, L4RE_PROTO_DATASPACE, L4::Type_info::Demand_t< 1 > > . . . . .	1296
L4Re::Dataspace . . . . .	1602
L4::Kobject_3t< Vbus, L4Re::Dataspace, L4Re::Inhibitor, L4Re::Event > . . . . .	1292
L4vbus::Vbus . . . . .	2001
L4::Kobject_t< Dbg_events, L4::Kobject, 0, L4::Type_info::Demand_t< 2 > > . . . . .	1296
L4::Kobject_t< Debug_obj, L4::Kobject, L4RE_PROTO_DEBUG > . . . . .	1296
L4Re::Debug_obj . . . . .	1617
L4::Kobject_t< Dma_space, L4::Kobject, PROTO, L4::Type_info::Demand_t< 1 > > . . . . .	1296
L4::Kobject_t< Inhibitor, L4::Kobject, L4RE_PROTO_INHIBITOR > . . . . .	1296
L4Re::Inhibitor . . . . .	1659
L4::Kobject_3t< Vbus, L4Re::Dataspace, L4Re::Inhibitor, L4Re::Event > . . . . .	1292
L4::Kobject_t< Itas, L4::Kobject, L4RE_PROTO_ITAS, L4::Type_info::Demand_t< 2 > > . . . . .	1296
L4Re::Itas . . . . .	1665
L4::Kobject_t< Mmio_space, L4::Kobject, L4RE_PROTO_MMIO_SPACE > . . . . .	1296
L4Re::Mmio_space . . . . .	1690
L4::Kobject_t< Namespace, L4::Kobject, L4RE_PROTO_NAMESPACE, L4::Type_info::Demand_t< 1 > > . . . . .	1296
L4Re::Namespace . . . . .	1695
L4::Kobject_t< Cmd_control, L4::Kobject, L4::PROTO_ANY, Type_info::Demand_t<> > . . . . .	1296
L4::Kobject_t< Parent, L4::Kobject, L4RE_PROTO_PARENT > . . . . .	1296
L4Re::Parent . . . . .	1707
L4::Kobject_t< Goos, L4::Kobject, L4RE_PROTO_GOOS > . . . . .	1296
L4Re::Video::Goos . . . . .	1895
L4::Kobject_2t< Derived, Base1, Base2, PROTO, S_DEMAND > . . . . .	1288
L4::Kobject_2t< Console, Video::Goos, Event, L4::PROTO_EMPTY > . . . . .	1288
L4Re::Console . . . . .	1594
L4::Kobject_2t< Debug_obj_t< BASE >, BASE, Debug_obj, L4::PROTO_EMPTY > . . . . .	1288
L4::Kobject_3t< Derived, Base1, Base2, Base3, PROTO, S_DEMAND > . . . . .	1292
L4::Kobject_demand< T > . . . . .	1295
L4::Kobject_t< Derived, Base, PROTO, S_DEMAND > . . . . .	1296
L4::Kobject_t< Remote_access, Dataspace, L4RE_PROTO_REMOTE_ACCESS > . . . . .	1296
L4::Kobject_typeid< T > . . . . .	1298
L4::Kobject_typeid< void > . . . . .	1302
L4::Kobject_x< Derived, ARGS > . . . . .	1305
L4::Kobject_x< Iommu, Proto_t< L4_PROTO_IOMMU >, Type_info::Demand_t< 1 > > . . . . .	1305
L4::Iommu . . . . .	1093
L4::Lock_guard . . . . .	1306
L4::Poll_timeout_counter . . . . .	1330
L4::Poll_timeout_kipclock . . . . .	1333
L4::Proto_t< P > . . . . .	1337
L4::Registry_iface . . . . .	1343
L4Re::Util::Object_registry . . . . .	1817
L4::Server< LOOP_HOOKS > . . . . .	1366
L4::String . . . . .	1390
L4::Thread::Attr . . . . .	1419
L4::Thread::Modify_senders . . . . .	1425
L4::Type_info . . . . .	1435
L4::Type_info::Demand . . . . .	1436

L4::Type_info::Demand_t< __l::Max< Kobject_typeid< T1 >Demand::Caps, Kobject_demand< T2... >Caps >Res, Kobject_typeid< T1 >Demand::Flags Kobject_demand< T2... >Flags, __l::Max< Kobject_typeid< T1 >Demand::Mem, Kobject_demand< T2... >Mem >Res, __l::Max< Kobject_typeid< T1 >Demand::Ports, Kobject_demand< T2... >Ports >Res >	1440
L4::Type_info::Demand_union_t< Kobject_typeid< T1 >Demand, Kobject_demand< T2... > >	1443
L4::Type_info::Demand_t< __l::Max< D1::Caps, D2::Caps >Res, D1::Flags D2Flags, __l::Max< D1::Mem, D2::Mem >Res, __l::Max< D1::Ports, D2::Ports >Res >	1440
L4::Type_info::Demand_union_t< D1, D2 >	1443
L4::Type_info::Demand_t< CAPS, FLAGS, MEM, PORTS >	1440
L4::Typeid::Detail::_Rpc< OPCODE, O, Default_op< R > >Rpc< Y >	1448
L4::Typeid::Detail::_Rpc< OPCODE, O, R, X... >Rpc< Y >	1451
L4::Typeid::Detail::Rpc_end	1452
L4::Typeid::Detail::type< OPCODE, 1,... >	1447
L4::Typeid::Detail::_Rpc< void, 0, OPERATION >	1447
L4::Typeid::Rpc_nocode< OPERATION >	1455
L4::Typeid::Detail::_Rpc< L4::Opcode, 0, RPCS... >	1447
L4::Typeid::Rpc< set_status_t, config_queue_t, register_ds_t, device_config_t, device_← notification_irq_t >	1457
L4::Typeid::Rpc< execute_t >	1457
L4::Typeid::Rpc< num_interfaces_t, interface_t, supports_t >	1457
L4::Typeid::Rpc< map_t, clear_t, info_t, copy_in_t, allocate_t, map_info_t >	1457
L4::Typeid::Rpc< request_backtrace_t >	1457
L4::Typeid::Rpc< map_t, unmap_t, associate_t, disassociate_t >	1457
L4::Typeid::Rpc< get_buffer_t, get_num_streams_t, get_stream_info_t, get_stream_info_for_id← t, get_axis_info_t, get_stream_state_for_id_t >	1457
L4::Typeid::Rpc< acquire_t, release_t, next_lock_info_t >	1457
L4::Typeid::Rpc< register_thread_t, unregister_thread_t, sigaction_t, sigaltstack_t, sigprocmask← t, sigpending_t, settimer_t, gettimer_t, raise_t >	1457
L4::Typeid::Rpc< info_t >	1457
L4::Typeid::Rpc< mmio_read_t, mmio_write_t >	1457
L4::Typeid::Rpc< query_t, register_obj_t, unlink_t >	1457
L4::Typeid::Rpc< signal_t >	1457
L4::Typeid::Rpc< get_random_t >	1457
L4::Typeid::Rpc< read_mem_t, write_mem_t, terminate_t >	1457
L4::Typeid::Rpc< attach_t, detach_t, find_t, reserve_area_t, free_area_t, get_regions_t, get← areas_t, get_info_t >	1457
L4::Typeid::Rpc< info_t, get_static_buffer_t, create_buffer_t, create_view_t, delete_buffer← t, delete_view_t, view_info_t, set_view_info_t, view_stack_t, view_refresh_t, refresh_t >	1457
L4::Typeid::Rpc< RPCS >	1457
L4::Typeid::Detail::_Rpc< OPCODE_TYPE, 0, RPCS... >	1447
L4::Typeid::Rpc_code< OPCODE_TYPE >F< RPCS >	1460
L4::Typeid::Detail::_Rpc< l4_umword_t, 0, ARG... >	1447
L4::Typeid::Rpc_sys< bind_thread_t, get_infos_t >	1463
L4::Typeid::Rpc_sys< bind_t, unbind_t, info_t, msi_info_t, unmask_t, mask_t, set_mode_t >	1463
L4::Typeid::Rpc_sys< system_suspend_t, system_shutdown_t, cpu_allow_shutdown_t, cpu← enable_t, cpu_disable_t >	1463
L4::Typeid::Rpc_sys< bind_thread_t >	1463
L4::Typeid::Rpc_sys< info_t, run_thread_t, idle_time_t >	1463
L4::Typeid::Rpc_sys< ARG >	1463
L4::Typeid::Detail::_Rpc< OPCODE, O, R, X... >	1448
L4::Typeid::Detail::_Rpc< OPCODE, O, X >	1447
L4::Typeid::Rpc_nocode< call_t >	1455
L4::Typeid::Rpc_nocode< exception_t >	1455
L4::Typeid::Rpc_nocode< create_t >	1455
L4::Typeid::Rpc_nocode< io_page_fault_t >	1455
L4::Typeid::Rpc_nocode< page_fault_t >	1455
L4::Typeid::Rpc_nocode< debug_t >	1455

L4::Typeid::P_dispatch< LIST > . . . . .	1452
L4::Typeid::Raw_ipc< CLASS > . . . . .	1453
L4::Typeid::Rpcs_code< OPCODE_TYPE > . . . . .	1459
L4::Types::__Add_rvalue_reference_helper< T, typename > . . . . .	1465
L4::Types::__Add_rvalue_reference_helper< T, Void< T && > > . . . . .	1466
L4::Types::__Underlying_type_helper< T, bool > . . . . .	1468
L4::Types::Underlying_type< T > . . . . .	1497
L4::Types::__Underlying_type_helper< T, false > . . . . .	1469
L4::Types::Add_rvalue_reference< T > . . . . .	1471
L4::Types::Bool< V > . . . . .	1472
L4::Types::Bool< false > . . . . .	1472
L4::Types::False . . . . .	1473
Enum_bitops::Has_marker< T, Void< decltype(enum_bitops_enable(declval< T >()))> > . . . . .	989
Enum_bitops::Has_marker< typename, typename > . . . . .	986
L4::Types::Same< A, B > . . . . .	1492
L4::Types::Bool< l1::Proto !=PROTO_EMPTY &&l1::Proto==l2::Proto > . . . . .	1472
L4::Types::Bool< true > . . . . .	1472
L4::Types::True . . . . .	1494
L4::ipc::Msg::ls_valid_rpc_type< A * > . . . . .	1156
Enum_bitops::Has_marker< T, Void< decltype(enum_bitops_enable(declval< T >()))> > . . . . .	989
L4::ipc::Msg::ls_valid_rpc_type< T > . . . . .	1156
L4::Types::Flags< BITS_ENUM, UNDERLYING > . . . . .	1476
L4::Types::Flags_ops_t< DT > . . . . .	1480
L4::Types::Flags_ops_t< Flags > . . . . .	1480
L4::Types::Flags_ops_t< Flags_t< DT, T > > . . . . .	1480
L4::Types::Flags_t< DT, T > . . . . .	1483
L4::Types::Int_for_size< SIZE, bool > . . . . .	1487
L4::Types::Int_for_type< T > . . . . .	1488
L4::Types::Integral_constant< T, Value > . . . . .	1489
Enum_bitops::Enable< T > . . . . .	985
L4::Types::Integral_constant< bool, __is_enum(T)> . . . . .	1489
L4::Types::ls_enum< T > . . . . .	1490
L4::Uart . . . . .	1498
L4::Uart_apb . . . . .	1505
l4_buf_regs_t . . . . .	1527
l4_exc_regs_t . . . . .	1528
l4_fpage_t . . . . .	1531
l4_icu_info_t . . . . .	1532
L4::Icu::Info . . . . .	1085
l4_icu_msi_info_t . . . . .	1533
l4_kernel_info_mem_desc_t . . . . .	1534
l4_kernel_info_t . . . . .	1535
l4_msg_regs_t . . . . .	1536
l4_msgtag_t . . . . .	1537
l4_sched_cpu_set_t . . . . .	1540
l4_sched_param_t . . . . .	1544
l4_snd_fpage_t . . . . .	1545
l4_thread_regs_t . . . . .	1546
l4_timeout_s . . . . .	1547
l4_timeout_t . . . . .	1548
l4_vcon_attr_t . . . . .	1549
l4_vcpu_arch_state_t . . . . .	1551
l4_vcpu_ipc_regs_t . . . . .	1551
l4_vcpu_regs_t . . . . .	1553
l4_vcpu_state_t . . . . .	1556
L4vcpu::Vcpu . . . . .	2016

<a href="#">l4_vm_svm_vmcb_control_area</a>	<a href="#">1560</a>
<a href="#">l4_vm_svm_vmcb_state_save_area</a>	<a href="#">1560</a>
<a href="#">l4_vm_svm_vmcb_state_save_area_seg</a>	<a href="#">1562</a>
<a href="#">l4_vm_svm_vmcb_t</a>	<a href="#">1562</a>
<a href="#">l4_vm_tz_state</a>	<a href="#">1564</a>
<a href="#">l4_vm_vmx_vcpu_infos_t</a>	<a href="#">1564</a>
<a href="#">l4_vm_vmx_vcpu_state_t</a>	<a href="#">1565</a>
<a href="#">l4_vm_vmx_vcpu_vmcs_t</a>	<a href="#">1567</a>
<a href="#">l4_vmx_offset_table_t</a>	<a href="#">1568</a>
<a href="#">L4drivers::Register_block&lt; MAX_BITS, BLOCK &gt;</a>	<a href="#">1572</a>
<a href="#">L4drivers::Register_block_base&lt; MAX_BITS &gt;</a>	<a href="#">1576</a>
<a href="#">L4drivers::Register_block_impl&lt; BASE, MAX_BITS &gt;</a>	<a href="#">1577</a>
<a href="#">L4drivers::Register_block_impl&lt; Mmio_register_block&lt; 32 &gt;, 32 &gt;</a>	<a href="#">1577</a>
<a href="#">L4drivers::Mmio_register_block&lt; MAX_BITS &gt;</a>	<a href="#">1570</a>
<a href="#">L4drivers::Register_block_tmpl&lt; BLOCK &gt;</a>	<a href="#">1579</a>
<a href="#">L4drivers::Register_block_tmpl&lt; Register_block_base&lt; MAX_BITS &gt; &gt;</a>	<a href="#">1579</a>
<a href="#">L4drivers::Register_block_tmpl&lt; Register_block_base&lt; MAX_BITS &gt; const &gt;</a>	<a href="#">1579</a>
<a href="#">L4drivers::Ro_register_block&lt; MAX_BITS, BLOCK &gt;</a>	<a href="#">1586</a>
<a href="#">L4drivers::Ro_register_tmpl&lt; BITS, BLOCK &gt;</a>	<a href="#">1588</a>
<a href="#">L4drivers::Register_tmpl&lt; MAX_BITS, Block &gt;</a>	<a href="#">1580</a>
<a href="#">L4drivers::Register_tmpl&lt; BITS, BLOCK &gt;</a>	<a href="#">1580</a>
<a href="#">L4Re::Cap_alloc</a>	<a href="#">1591</a>
<a href="#">L4Re::Util::Cap_alloc</a>	<a href="#">1748</a>
<a href="#">L4Re::Core::Ref_ptr&lt; T, CNT &gt;</a>	<a href="#">1597</a>
<a href="#">L4Re::Dataspace::F</a>	<a href="#">1615</a>
<a href="#">L4Re::Dataspace::Stats</a>	<a href="#">1616</a>
<a href="#">L4Re::Default_event_payload</a>	<a href="#">1621</a>
<a href="#">L4Re::Env</a>	<a href="#">1629</a>
<a href="#">L4Re::Event_buffer_t&lt; PAYLOAD &gt;</a>	<a href="#">1654</a>
<a href="#">L4Re::Event_buffer_t&lt; PAYLOAD &gt;Event</a>	<a href="#">1658</a>
<a href="#">L4Re::Event_buffer_t&lt; Default_event_payload &gt;</a>	<a href="#">1654</a>
<a href="#">L4Re::Util::Event_buffer_t&lt; Default_event_payload &gt;</a>	<a href="#">1798</a>
<a href="#">L4Re::Util::Event_buffer_consumer_t&lt; Default_event_payload &gt;</a>	<a href="#">1795</a>
<a href="#">L4Re::Event_buffer_t&lt; PAYLOAD &gt;</a>	<a href="#">1654</a>
<a href="#">L4Re::Util::Event_buffer_t&lt; PAYLOAD &gt;</a>	<a href="#">1798</a>
<a href="#">L4Re::Util::Event_buffer_consumer_t&lt; PAYLOAD &gt;</a>	<a href="#">1795</a>
<a href="#">L4Re::Mem_alloc::Stats</a>	<a href="#">1687</a>
<a href="#">L4Re::Rm::Area</a>	<a href="#">1737</a>
<a href="#">L4Re::Rm::F</a>	<a href="#">1737</a>
<a href="#">L4Re::Rm::Region</a>	<a href="#">1739</a>
<a href="#">L4Re::Rm::Unique_region&lt; T &gt;</a>	<a href="#">1740</a>
<a href="#">L4Re::Smart_cap_auto&lt; Unmap_flags &gt;</a>	<a href="#">1746</a>
<a href="#">L4Re::Smart_count_cap&lt; Unmap_flags &gt;</a>	<a href="#">1746</a>
<a href="#">L4Re::Util::Bitmap_base</a>	<a href="#">1756</a>
<a href="#">cxx::Bitmap&lt; BITS &gt;</a>	<a href="#">830</a>
<a href="#">L4Re::Util::Bitmap_base::Bit</a>	<a href="#">1764</a>
<a href="#">L4Re::Util::Bitmap_base::Char&lt; BITS &gt;</a>	<a href="#">1764</a>
<a href="#">L4Re::Util::Bitmap_base::Word&lt; BITS &gt;</a>	<a href="#">1765</a>
<a href="#">L4Re::Util::Cap_alloc_base</a>	<a href="#">1778</a>
<a href="#">L4Re::Util::Counter&lt; COUNTER &gt;</a>	<a href="#">1779</a>
<a href="#">L4Re::Util::Counter_atomic&lt; COUNTER &gt;</a>	<a href="#">1780</a>
<a href="#">L4Re::Util::Counting_cap_alloc&lt; COUNTERTYPE, Dbg &gt;</a>	<a href="#">1782</a>
<a href="#">L4Re::Util::Dataspace_svr</a>	<a href="#">1788</a>
<a href="#">L4Re::Util::Event_svr&lt; SVR &gt;</a>	<a href="#">1802</a>
<a href="#">L4Re::Util::Event_t&lt; PAYLOAD &gt;</a>	<a href="#">1804</a>
<a href="#">L4Re::Util::Item_alloc_base</a>	<a href="#">1808</a>

L4Re::Util::Names::Name_space	1812
L4Re::Util::Ref_cap< T >	1824
L4Re::Util::Ref_del_cap< T >	1826
L4Re::Util::Smart_cap_auto< Unmap_flags >	1833
L4Re::Util::Smart_count_cap< Unmap_flags >	1834
L4Re::Util::Vcon_svr< SVR >	1835
L4Re::Util::Video::Goos_svr	1836
L4Re::Vfs::Directory	1848
L4Re::Vfs::File	1853
L4Re::Vfs::Be_file	1840
L4Re::Vfs::File_system	1857
L4Re::Vfs::Be_file_system	1845
L4Re::Vfs::Fs	1859
L4Re::Vfs::Ops	1874
L4Re::Vfs::Generic_file	1864
L4Re::Vfs::File	1853
L4Re::Vfs::Mman	1873
L4Re::Vfs::Ops	1874
L4Re::Vfs::Regular_file	1877
L4Re::Vfs::File	1853
L4Re::Vfs::Special_file	1887
L4Re::Vfs::File	1853
L4Re::Video::Color_component	1890
L4Re::Video::Goos::Info	1905
L4Re::Video::Pixel_info	1907
L4Re::Video::View	1918
L4Re::Video::View::Info	1925
l4re_aux_t	1927
l4re_ds_stats_t	1928
l4re_elf_aux_mword_t	1928
l4re_elf_aux_t	1929
l4re_elf_aux_vma_t	1930
l4re_env_cap_entry_t	1930
l4re_env_t	1932
l4re_event_t	1935
l4re_video_color_component_t	1936
l4re_video_goos_info_t	1936
l4re_video_pixel_info_t	1938
l4re_video_view_info_t	1939
l4re_video_view_t	1941
l4shmc_ringbuf_head_t	1942
l4shmc_ringbuf_t	1943
l4util_l4mod_info	1944
l4util_l4mod_mod	1946
l4util_mb_addr_range_t	1947
l4util_mb_apm_t	1948
l4util_mb_drive_t	1948
l4util_mb_info_t	1949
l4util_mb_mod_t	1951
l4util_mb_vbe_ctrl_t	1952
l4util_mb_vbe_mode_t	1952
L4vbus::Gpio_module::Pin_slice	1973
L4vbus::Pm< DEC >	1998
L4vbus::Pm< Device >	1998
L4vbus::Device	1956
L4vbus::Gpio_module	1966

L4vbus::Gpio_pin . . . . .	1973
L4vbus::Icu . . . . .	1982
L4vbus::Pci_dev . . . . .	1986
L4vbus::Pci_host_bridge . . . . .	1992
l4vbus_device_t . . . . .	2012
l4vbus_resource_t . . . . .	2013
L4vcpu::State . . . . .	2014
L4virtio::Driver::Block_device::Handle . . . . .	2047
L4virtio::Driver::Device . . . . .	2047
L4virtio::Driver::Block_device . . . . .	2039
L4virtio::Driver::Virtio_net_device . . . . .	2060
L4virtio::Driver::Virtio_net_device::Packet . . . . .	2069
L4virtio::Ptr< T > . . . . .	2079
L4virtio::Svr::Bad_descriptor . . . . .	2082
L4virtio::Svr::Block_request< Ds_data > . . . . .	2093
L4virtio::Svr::Console::Control_message . . . . .	2095
L4virtio::Svr::Console::Control_request . . . . .	2097
L4virtio::Svr::Console::Port . . . . .	2121
L4virtio::Svr::Console::Device_port . . . . .	2112
L4virtio::Svr::Console::Port::Transition . . . . .	2125
L4virtio::Svr::Data_buffer . . . . .	2143
Buffer . . . . .	785
L4virtio::Svr::Dev_config . . . . .	2147
L4virtio::Svr::Dev_features . . . . .	2159
L4virtio::Svr::Console::Features . . . . .	2116
L4virtio::Svr::Dev_status . . . . .	2162
L4virtio::Svr::Device_t< DATA > . . . . .	2165
L4virtio::Svr::Device_t< Ds_data > . . . . .	2165
L4virtio::Svr::Block_dev_base< Ds_data > . . . . .	2084
L4virtio::Svr::Device_t< No_custom_data > . . . . .	2165
L4virtio::Svr::Console::Virtio_con . . . . .	2126
L4virtio::Svr::Console::Device . . . . .	2098
L4virtio::Svr::Scmi::Scmi_dev . . . . .	2204
L4virtio::Svr::Virtio_gpio< Request_handler, Epiface > . . . . .	2210
L4virtio::Svr::Virtio_i2c< Request_handler, Epiface > . . . . .	2222
L4virtio::Svr::Virtio_rng< Rnd_state, Epiface > . . . . .	2233
L4virtio::Svr::Virtio_spi< Spi_request_handler, Epiface > . . . . .	2243
Virtio_net . . . . .	2345
L4virtio::Svr::Driver_mem_list_t< DATA > . . . . .	2172
L4virtio::Svr::Driver_mem_region_t< DATA > . . . . .	2178
L4virtio::Svr::Driver_mem_region_t< Ds_data > . . . . .	2178
L4virtio::Svr::Driver_mem_region_t< No_custom_data > . . . . .	2178
L4virtio::Svr::Request_processor . . . . .	2185
L4virtio::Svr::Virtio_gpio< Request_handler, Epiface >Request_processor . . . . .	2219
L4virtio::Svr::Virtio_i2c< Request_handler, Epiface >Request_processor . . . . .	2230
L4virtio::Svr::Virtio_rng< Rnd_state, Epiface >Request_processor . . . . .	2241
L4virtio::Svr::Virtio_spi< Spi_request_handler, Epiface >Request_processor . . . . .	2252
L4virtio::Svr::Scmi::Base_attr_t . . . . .	2192
L4virtio::Svr::Scmi::Performance_attr_t . . . . .	2198
L4virtio::Svr::Scmi::Performance_describe_level_t . . . . .	2199
L4virtio::Svr::Scmi::Performance_describe_levels_n_t . . . . .	2199
L4virtio::Svr::Scmi::Performance_domain_attr_t . . . . .	2201
L4virtio::Svr::Scmi::Proto< OBSERV > . . . . .	2203
L4virtio::Svr::Scmi::Proto< Scmi_dev > . . . . .	2203
L4virtio::Svr::Scmi::Base_proto . . . . .	2193
L4virtio::Svr::Scmi::Perf_proto . . . . .	2195



L4virtio::Svr::Scmi::Scmi_hdr_t . . . . .	2208
L4virtio::Svr::Virtio_gpio< Request_handler, Epiface >Irq_handler . . . . .	2218
L4virtio::Svr::Virtqueue::Head_desc . . . . .	2267
L4virtio::Virtqueue . . . . .	2270
L4virtio::Driver::Virtqueue . . . . .	2070
L4virtio::Svr::Virtqueue . . . . .	2255
L4virtio::Virtqueue::Avail . . . . .	2287
L4virtio::Virtqueue::Avail::Flags . . . . .	2288
L4virtio::Virtqueue::Desc . . . . .	2289
L4virtio::Virtqueue::Desc::Flags . . . . .	2291
L4virtio::Virtqueue::Used . . . . .	2293
L4virtio::Virtqueue::Used::Flags . . . . .	2294
L4virtio::Virtqueue::Used_elem . . . . .	2296
l4virtio_block_config_t . . . . .	2297
l4virtio_block_discard_t . . . . .	2298
l4virtio_block_header_t . . . . .	2299
l4virtio_config_hdr_t . . . . .	2300
l4virtio_config_queue_t . . . . .	2301
l4virtio_input_absinfo_t . . . . .	2302
l4virtio_input_config_t . . . . .	2303
l4virtio_input_devids_t . . . . .	2303
l4virtio_input_event_t . . . . .	2304
l4virtio_net_config_t . . . . .	2305
l4virtio_net_header_t . . . . .	2305
Mac_addr . . . . .	2312
Mac_table< Size > . . . . .	2312
Net_transfer . . . . .	2315
Rm::Area . . . . .	2332
Rm::F . . . . .	2333
Rm::Region . . . . .	2335
Rm::Unique_region< T > . . . . .	2336
Virtio_net_request . . . . .	2350
Virtio_switch . . . . .	2353
Virtio_vlan_mangle . . . . .	2358



# Chapter 11

## Data Structure Index

### 11.1 Data Structures

Here are the data structures with brief descriptions:

<a href="#">Buffer</a>	
Data buffer used to transfer packets	785
<a href="#">cxx::arith::Ld&lt; V &gt;</a>	
Computes the binary logarithm of the given number at compile time	787
<a href="#">cxx::Avl_map&lt; KEY_TYPE, DATA_TYPE, COMPARE, ALLOC &gt;</a>	
AVL tree based associative container	788
<a href="#">cxx::Avl_set&lt; ITEM_TYPE, COMPARE, ALLOC &gt;</a>	
AVL set for simple comparable items	794
<a href="#">cxx::Avl_tree&lt; Node, Get_key, Compare &gt;</a>	
A generic AVL tree	798
<a href="#">cxx::Avl_tree_node</a>	
Node of an AVL tree	806
<a href="#">cxx::Base_slab&lt; Obj_size, Slab_size, Max_free, Alloc &gt;</a>	
Basic slab allocator	808
<a href="#">cxx::Base_slab&lt; Obj_size, Slab_size, Max_free, Alloc &gt;::Slab_i</a>	
Type of a slab	812
<a href="#">cxx::Base_slab_static&lt; Obj_size, Slab_size, Max_free, Alloc &gt;</a>	
Merged slab allocator (allocators for objects of the same size are merged together)	813
<a href="#">cxx::Bitfield&lt; T, LSB, MSB &gt;</a>	
Definition for a member (part) of a bit field	818
<a href="#">cxx::Bitfield&lt; T, LSB, MSB &gt;::Value&lt; TT &gt;</a>	
Internal helper type	826
<a href="#">cxx::Bitfield&lt; T, LSB, MSB &gt;::Value_base&lt; TT &gt;</a>	
Internal helper type	827
<a href="#">cxx::Bitfield&lt; T, LSB, MSB &gt;::Value_unshifted&lt; TT &gt;</a>	
Internal helper type	828
<a href="#">cxx::Bitmap&lt; BITS &gt;</a>	
A static bitmap	830
<a href="#">cxx::Bitmap_base</a>	
Basic bitmap abstraction	834
<a href="#">cxx::Bitmap_base::Bit</a>	
A writable bit in a bitmap	847
<a href="#">cxx::Bitmap_base::Char&lt; BITS &gt;</a>	
Helper abstraction for a byte contained in the bitmap	847
<a href="#">cxx::Bitmap_base::Word&lt; BITS &gt;</a>	
Helper abstraction for a word contained in the bitmap	848

<a href="#">cxx::Bits::Avl_map_get_key&lt; KEY_TYPE &gt;</a>	
Key-getter for <a href="#">Avl_map</a>	849
<a href="#">cxx::Bits::Avl_set_get_key&lt; KEY_TYPE &gt;</a>	
Internal, key-getter for <a href="#">Avl_set</a> nodes	850
<a href="#">cxx::Bits::Avl_set_iter&lt; Node, Key, Node_op &gt;</a>	
Generic iterator for the AVL-tree based set	850
<a href="#">cxx::Bits::Base_avl_set&lt; ITEM_TYPE, COMPARE, ALLOC, GET_KEY &gt;</a>	
AVL set with internally managed nodes	854
<a href="#">cxx::Bits::Base_avl_set&lt; ITEM_TYPE, COMPARE, ALLOC, GET_KEY &gt;::Node</a>	
A smart pointer to a tree item	864
<a href="#">cxx::Bits::Basic_list&lt; POLICY &gt;</a>	
Internal: Common functions for all head-based list implementations	866
<a href="#">cxx::Bits::Bst&lt; Node, Get_key, Compare &gt;</a>	
Basic binary search tree (BST)	869
<a href="#">cxx::Bits::Bst_node</a>	
Basic type of a node in a binary search tree (BST)	882
<a href="#">cxx::Bits::Direction</a>	
The direction to go in a binary search tree	884
<a href="#">cxx::Bits::Smart_ptr_list&lt; ITEM &gt;</a>	
List of smart-pointer-managed objects	886
<a href="#">cxx::Bits::Smart_ptr_list_item&lt; T, STORE_T &gt;</a>	
List item for an arbitrary item in a <a href="#">Smart_ptr_list</a>	889
<a href="#">cxx::Elide_dtor&lt; T &gt;</a>	
Wrapper class to remove destructor calls	891
<a href="#">cxx::H_list&lt; T, POLICY &gt;</a>	
General double-linked list of unspecified <a href="#">cxx::H_list_item</a> elements	892
<a href="#">cxx::H_list_item_t&lt; ELEM_TYPE &gt;</a>	
Basic element type for a double-linked <a href="#">H_list</a>	899
<a href="#">cxx::H_list_t&lt; T &gt;</a>	
Double-linked list of typed <a href="#">H_list_item_t</a> elements	902
<a href="#">cxx::List&lt; D, Alloc &gt;</a>	
Doubly linked list, with internal allocation	906
<a href="#">cxx::List&lt; D, Alloc &gt;::Iter</a>	
Iterator	908
<a href="#">cxx::List_alloc</a>	
Standard list-based allocator	909
<a href="#">cxx::List_item</a>	
Basic list item	913
<a href="#">cxx::List_item::Iter</a>	
Iterator for a list of <a href="#">ListItem</a> -s	916
<a href="#">cxx::List_item::T_iter&lt; T, Poly &gt;</a>	
Iterator for derived classes from <a href="#">ListItem</a>	918
<a href="#">cxx::Lt_functor&lt; Obj &gt;</a>	
Generic comparator class that defaults to the less-than operator	920
<a href="#">cxx::New_allocator&lt; _Type &gt;</a>	
Standard allocator based on <code>operator new ()</code>	920
<a href="#">cxx::Nothrow</a>	
Helper type to distinguish the <code>operator new</code> version that does not throw exceptions	922
<a href="#">cxx::Pair&lt; First, Second &gt;</a>	
Pair of two values	922
<a href="#">cxx::Pair_first_compare&lt; Cmp, Typ &gt;</a>	
Comparison functor for <a href="#">Pair</a>	925
<a href="#">cxx::Ref_obj_list_item&lt; T &gt;</a>	
Item for list linked via <a href="#">cxx::Ref_ptr</a> with default reference counting	927
<a href="#">cxx::Ref_ptr&lt; T, CNT &gt;</a>	
A reference-counting pointer with automatic cleanup	929
<a href="#">cxx::S_list&lt; T, POLICY &gt;</a>	
Simple single-linked list	934

<a href="#">cxx::Slab&lt; Type, Slab_size, Max_free, Alloc &gt;</a>	
Slab allocator for object of type <code>Type</code>	937
<a href="#">cxx::Slab_static&lt; Type, Slab_size, Max_free, Alloc &gt;</a>	
Merged slab allocator (allocators for objects of the same size are merged together)	942
<a href="#">cxx::static_vector&lt; T, IDX &gt;</a>	
Simple encapsulation for a dynamically allocated array	946
<a href="#">cxx::String</a>	
Allocation free string class with explicit length field	947
<a href="#">cxx::Weak_ref&lt; T &gt;</a>	
Typed weak reference to an object of type <code>T</code>	955
<a href="#">cxx::Weak_ref_base</a>	
Generic (base) weak reference to some object	957
<a href="#">cxx::Weak_ref_base::List</a>	
The list type for keeping all weak references to an object	960
<a href="#">Elf32_Auxv</a>	
Auxiliary vector (32-bit)	964
<a href="#">Elf32_Dyn</a>	
ELF32 dynamic entry	965
<a href="#">Elf32_Ehdr</a>	
ELF32 header	966
<a href="#">Elf32_Phdr</a>	
ELF32 program header	969
<a href="#">Elf32_Rel</a>	
ELF32 relocation entry w/o addend	970
<a href="#">Elf32_Rela</a>	
ELF32 relocation entry w/ addend	971
<a href="#">Elf32_Shdr</a>	
ELF32 section header	972
<a href="#">Elf32_Sym</a>	
ELF32 symbol table entry	974
<a href="#">Elf64_Auxv</a>	
Auxiliary vector (64-bit)	975
<a href="#">Elf64_Dyn</a>	
ELF64 dynamic entry	976
<a href="#">Elf64_Ehdr</a>	
ELF64 header	977
<a href="#">Elf64_Phdr</a>	
ELF64 program header	979
<a href="#">Elf64_Rel</a>	
ELF64 relocation entry w/o addend	981
<a href="#">Elf64_Rela</a>	
ELF64 relocation entry w/ addend	981
<a href="#">Elf64_Shdr</a>	
ELF64 section header	982
<a href="#">Elf64_Sym</a>	
ELF64 symbol table entry	984
<a href="#">Enum_bitops::Enable&lt; T &gt;</a>	
Check whether the given enum type opts in for the bitwise operators	985
<a href="#">Enum_bitops::Has_marker&lt; typename, typename &gt;</a>	
Marker for the opt-in ADL function	986
<a href="#">Enum_bitops::Has_marker&lt; T, Void&lt; decltype(enum_bitops_enable(declval&lt; T &gt;()))&gt; &gt;</a>	
Marker for the opt-in ADL function	989
<a href="#">L4::Alloc_list</a>	
A simple list-based allocator	991
<a href="#">L4::Arm_smccc</a>	
Wrapper for function calls that follow the ARM SMC/HVC calling convention	992
<a href="#">L4::Base_exception</a>	
Base class for all exceptions, thrown by the <a href="#">L4Re</a> framework	994

<a href="#">L4::Basic_registry</a>	
This registry returns the corresponding server object based on the label of an <a href="#">lpc_gate</a>	996
<a href="#">L4::Bounds_error</a>	
Access out of bounds	999
<a href="#">L4::Cap&lt; T &gt;</a>	
C++ interface for capabilities	1002
<a href="#">L4::Cap_base</a>	
Base class for all kinds of capabilities	1008
<a href="#">L4::Com_error</a>	
Error conditions during IPC	1021
<a href="#">L4::Debugger</a>	
C++ kernel debugger API	1024
<a href="#">L4::Element_already_exists</a>	
Exception for duplicate element insertions	1034
<a href="#">L4::Element_not_found</a>	
Exception for a failed lookup (element not found)	1038
<a href="#">L4::Epiface</a>	
Base class for interface implementations	1041
<a href="#">L4::Epiface_t&lt; Derived, IFACE, BASE, bool &gt;</a>	
Epiface implementation for Kobject-based interface implementations	1046
<a href="#">L4::Epiface_t0&lt; RPC_IFACE, BASE &gt;</a>	
Epiface mixin for generic Kobject-based interfaces	1049
<a href="#">L4::Exception</a>	
Exception interface	1052
<a href="#">L4::Exception_tracer</a>	
Back-trace support for exceptions	1054
<a href="#">L4::Factory</a>	
C++ Factory interface, see <a href="#">Factory</a> for the C interface	1055
<a href="#">L4::Factory::Lstr</a>	
Special type to add a pascal string into the factory create stream	1066
<a href="#">L4::Factory::Nil</a>	
Special type to add a void argument into the factory create stream	1068
<a href="#">L4::Factory::S</a>	
Stream class for the <a href="#">create()</a> argument stream	1068
<a href="#">L4::lcu</a>	
C++ lcu interface, see <a href="#">Interrupt controller</a> for the C interface	1075
<a href="#">L4::lcu::Info</a>	
This class encapsulates information about an ICU	1085
<a href="#">L4::Invalid_capability</a>	
Indicates that an invalid object was invoked	1087
<a href="#">L4::lo_pager</a>	
lo_pager interface	1090
<a href="#">L4::lommu</a>	
Interface for IO-MMUs used for DMA remapping	1093
<a href="#">L4::IOModifier</a>	
Modifier class for the IO stream	1098
<a href="#">L4::lpc::Array&lt; ELEM_TYPE, LEN_TYPE &gt;</a>	
Array data type for dynamically sized arrays in RPCs	1098
<a href="#">L4::lpc::Array_in_buf&lt; ELEM_TYPE, LEN_TYPE, MAX &gt;</a>	
Server-side copy in buffer for Array	1101
<a href="#">L4::lpc::Array_ref&lt; ELEM_TYPE, LEN_TYPE &gt;</a>	
Array reference data type for arrays located in the message	1104
<a href="#">L4::lpc::As_value&lt; T &gt;</a>	
Pass the argument as plain data value	1105
<a href="#">L4::lpc::Call</a>	
RPC attribute for a standard RPC call	1106
<a href="#">L4::lpc::Call_t&lt; RIGHTS &gt;</a>	
RPC attribute for an RPC call with required rights	1107

<a href="#">L4::lpc::Call_zero_send_timeout</a>	RPC attribute for an RPC call, with zero send timeout . . . . .	1108
<a href="#">L4::lpc::Cap&lt; T &gt;</a>	Capability type for RPC interfaces (see <a href="#">L4::Cap&lt;T&gt;</a> ) . . . . .	1109
<a href="#">L4::lpc::Gen_fpage</a>	Generic RPC base for typed message items . . . . .	1113
<a href="#">L4::lpc::In_out&lt; T &gt;</a>	Mark an argument as in-out argument . . . . .	1116
<a href="#">L4::lpc::Iostream</a>	Input/Output stream for IPC [un]marshalling . . . . .	1117
<a href="#">L4::lpc::Istream</a>	Input stream for IPC unmarshalling . . . . .	1127
<a href="#">L4::lpc::Msg::CInt_val_ops&lt; MTYPE, DIR, CLASS &gt;</a>	Defines client-side handling of 'MTYPE' as RPC argument . . . . .	1138
<a href="#">L4::lpc::Msg::Cls_buffer</a>	Marker type for receive buffer values . . . . .	1139
<a href="#">L4::lpc::Msg::Cls_data</a>	Marker type for data values . . . . .	1141
<a href="#">L4::lpc::Msg::Cls_item</a>	Marker type for item values . . . . .	1142
<a href="#">L4::lpc::Msg::Dir_in</a>	Marker type for input values . . . . .	1143
<a href="#">L4::lpc::Msg::Dir_out</a>	Marker type for output values . . . . .	1144
<a href="#">L4::lpc::Msg::Do_in_data</a>	Marker for Input data . . . . .	1145
<a href="#">L4::lpc::Msg::Do_in_items</a>	Marker for Input items . . . . .	1146
<a href="#">L4::lpc::Msg::Do_out_data</a>	Marker for Output data . . . . .	1147
<a href="#">L4::lpc::Msg::Do_out_items</a>	Marker for Output items . . . . .	1148
<a href="#">L4::lpc::Msg::Do_rcv_buffers</a>	Marker for receive buffers . . . . .	1150
<a href="#">L4::lpc::Msg::Elem&lt; Array&lt; A, LEN &gt; &amp; &gt;</a>	Array as output argument . . . . .	1151
<a href="#">L4::lpc::Msg::Elem&lt; Array&lt; A, LEN &gt; &gt;</a>	Array as input arguments . . . . .	1152
<a href="#">L4::lpc::Msg::Elem&lt; Array_ref&lt; A, LEN &gt; &amp; &gt;</a>	Array_ref as output argument . . . . .	1153
<a href="#">L4::lpc::Msg::False</a>	False meta value . . . . .	1154
<a href="#">L4::lpc::Msg::Is_valid_rpc_type&lt; T &gt;</a>	Type trait defining a valid RPC parameter type . . . . .	1156
<a href="#">L4::lpc::Msg::Svr_arg_pack&lt; IPC_TYPE &gt;</a>	Server-side RPC arguments data structure used to provide arguments to the server-side implementation of an RPC function . . . . .	1158
<a href="#">L4::lpc::Msg::Svr_val_ops&lt; MTYPE, DIR, CLASS &gt;</a>	Defines server-side handling for MTYPE server arguments . . . . .	1158
<a href="#">L4::lpc::Msg::True</a>	True meta value . . . . .	1159
<a href="#">L4::lpc::Msg_ptr&lt; T &gt;</a>	Pointer to an element of type T in an <a href="#">lpc::Istream</a> . . . . .	1162
<a href="#">L4::lpc::Opt&lt; T &gt;</a>	Attribute for defining an optional RPC argument . . . . .	1163
<a href="#">L4::lpc::Ostream</a>	Output stream for IPC marshalling . . . . .	1165

<a href="#">L4::lpc::Out&lt; T &gt;</a>	Mark an argument as a output value in an RPC signature . . . . .	1171
<a href="#">L4::lpc::Rcv_fpage</a>	Non-small receive item . . . . .	1172
<a href="#">L4::lpc::Ret_array&lt; T &gt;</a>	Dynamically sized output array of type T . . . . .	1179
<a href="#">L4::lpc::Send_only</a>	RPC attribute for a send-only RPC . . . . .	1180
<a href="#">L4::lpc::Small_buf</a>	A receive item for receiving a single object capability . . . . .	1181
<a href="#">L4::lpc::Snd_fpage</a>	Send item or return item . . . . .	1183
<a href="#">L4::lpc::Str_cp_in&lt; T &gt;</a>	Abstraction for extracting a zero-terminated string from an <a href="#">lpc::Istream</a> . . . . .	1193
<a href="#">L4::lpc::Varg</a>	Variably sized RPC argument . . . . .	1194
<a href="#">L4::lpc::Varg_list&lt; MAX &gt;</a>	Self-contained list of variable-sized RPC parameters . . . . .	1200
<a href="#">L4::lpc::Varg_list_ref</a>	List of variable-sized RPC parameters as received by the server . . . . .	1203
<a href="#">L4::lpc::Varg_list_ref::Iterator</a>	Iterator for Valists . . . . .	1205
<a href="#">L4::lpc_gate</a>	The C++ IPC gate interface, see <a href="#">IPC-Gate API</a> for the C interface . . . . .	1207
<a href="#">L4::lpc_svr::Br_manager_no_buffers</a>	Empty implementation of <a href="#">Server_iface</a> . . . . .	1212
<a href="#">L4::lpc_svr::Compound_reply</a>	Mix in for LOOP_HOOKS to always use compound reply and wait . . . . .	1216
<a href="#">L4::lpc_svr::Dbg_dispatch&lt; R, Exc, Printer &gt;</a>	Dispatch helper that, in addition to what <a href="#">Exc_dispatch</a> does, prints exception messages . . . . .	1218
<a href="#">L4::lpc_svr::Default_loop_hooks</a>	Default LOOP_HOOKS . . . . .	1220
<a href="#">L4::lpc_svr::Default_setup_wait</a>	Mix in for LOOP_HOOKS for setup_wait no op . . . . .	1223
<a href="#">L4::lpc_svr::Default_timeout</a>	Mix in for LOOP_HOOKS to use a 0 send and a infinite receive timeout . . . . .	1224
<a href="#">L4::lpc_svr::Direct_dispatch&lt; R &gt;</a>	Direct dispatch helper, for forwarding dispatch calls to a registry <i>R</i> . . . . .	1226
<a href="#">L4::lpc_svr::Direct_dispatch&lt; R * &gt;</a>	Direct dispatch helper, for forwarding dispatch calls via a pointer to a registry <i>R</i> . . . . .	1228
<a href="#">L4::lpc_svr::Exc_dispatch&lt; R, Exc &gt;</a>	Dispatch helper wrapping try {} catch {} around the dispatch call . . . . .	1230
<a href="#">L4::lpc_svr::Ignore_errors</a>	Mix in for LOOP_HOOKS to ignore IPC errors . . . . .	1232
<a href="#">L4::lpc_svr::Server_iface</a>	Interface for server-loop related functions . . . . .	1233
<a href="#">L4::lpc_svr::Timeout</a>	Callback interface for <a href="#">Timeout_queue</a> . . . . .	1240
<a href="#">L4::lpc_svr::Timeout_queue</a>	Timeout queue to be used in l4re server loop . . . . .	1244
<a href="#">L4::lpc_svr::Timeout_queue_hooks&lt; HOOKS, BR_MAN &gt;</a>	Loop hooks mixin for integrating a timeout queue into the server loop . . . . .	1247
<a href="#">L4::Irq</a>	C++ <a href="#">Irq</a> interface, see <a href="#">IRQs</a> for the C interface . . . . .	1252
<a href="#">L4::Irq_eoi</a>	Interface for sending an unmask message to an object . . . . .	1262
<a href="#">L4::Irq_handler_object</a>	Server object base class for handling IRQ messages . . . . .	1265



<a href="#">L4::lrqep_t&lt; Derived, BASE, bool &gt;</a>	
Epiface implementation for interrupt handlers	1269
<a href="#">L4::Kip::Mem_desc</a>	
Memory descriptors stored in the kernel interface page	1273
<a href="#">L4::Kobject</a>	
Base class for all kinds of kernel objects and remote objects, referenced by capabilities	1284
<a href="#">L4::Kobject_2t&lt; Derived, Base1, Base2, PROTO, S_DEMAND &gt;</a>	
Helper class to create an <a href="#">L4Re</a> interface class that is derived from two base classes (see <a href="#">L4::Kobject_t</a> )	1288
<a href="#">L4::Kobject_3t&lt; Derived, Base1, Base2, Base3, PROTO, S_DEMAND &gt;</a>	
Helper class to create an <a href="#">L4Re</a> interface class that is derived from three base classes (see <a href="#">L4::Kobject_t</a> )	1292
<a href="#">L4::Kobject_demand&lt; T &gt;</a>	
Get the combined server-side resource requirements for all type T..	1295
<a href="#">L4::Kobject_t&lt; Derived, Base, PROTO, S_DEMAND &gt;</a>	
Helper class to create an <a href="#">L4Re</a> interface class that is derived from a single base class	1296
<a href="#">L4::Kobject_typeid&lt; T &gt;</a>	
Meta object for handling access to type information of Kobjects	1298
<a href="#">L4::Kobject_typeid&lt; void &gt;</a>	
Minimalistic ID for void interface	1302
<a href="#">L4::Kobject_x&lt; Derived, ARGS &gt;</a>	
Generic <a href="#">Kobject</a> inheritance template	1305
<a href="#">L4::Lock_guard</a>	
Basic lock guard implementation that prevents forgotten unlocks on exit paths from a method or a block of code	1306
<a href="#">L4::Meta</a>	
Meta interface that shall be implemented by each <a href="#">L4Re</a> object and gives access to the dynamic type information for <a href="#">L4Re</a> objects	1309
<a href="#">L4::Out_of_memory</a>	
Exception signalling insufficient memory	1315
<a href="#">L4::Pager</a>	
Pager interface including the <a href="#">lo_pager</a> interface	1319
<a href="#">L4::Platform_control</a>	
L4 C++ interface for controlling platform-wide properties, see <a href="#">Platform Control C API</a> for the C interface	1322
<a href="#">L4::Poll_timeout_counter</a>	
Evaluate an expression for a maximum number of times	1330
<a href="#">L4::Poll_timeout_kipclock</a>	
A polling timeout based on the <a href="#">L4Re</a> clock	1333
<a href="#">L4::Proto_t&lt; P &gt;</a>	
Data type for defining protocol numbers	1337
<a href="#">L4::Rcv_endpoint</a>	
Interface for kernel objects that allow to receive IPC from them	1337
<a href="#">L4::Registry_iface</a>	
Abstract interface for object registries	1343
<a href="#">L4::Runtime_error</a>	
Exception for an abstract runtime error	1348
<a href="#">L4::Scheduler</a>	
C++ interface of the <a href="#">Scheduler</a> kernel object, see <a href="#">Scheduler</a> for the C interface	1352
<a href="#">L4::Semaphore</a>	
C++ Kernel-provided semaphore interface, see <a href="#">Kernel-provided semaphore</a> for the C interface	1361
<a href="#">L4::Server&lt; LOOP_HOOKS &gt;</a>	
Basic server loop for handling client requests	1366
<a href="#">L4::Server_object</a>	
Abstract server object to be used with <a href="#">L4::Server</a> and <a href="#">L4::Basic_registry</a>	1372
<a href="#">L4::Server_object_t&lt; IFACE, BASE &gt;</a>	
Base class (template) for server implementing server objects	1377

<a href="#">L4::Server_object_x&lt; Derived, IFACE, BASE &gt;</a>	
Helper class to implement p_dispatch based server objects	1382
<a href="#">L4::Smart_cap&lt; T, SMART &gt;</a>	
Smart capability class	1386
<a href="#">L4::String</a>	
A null-terminated string container class	1390
<a href="#">L4::Task</a>	
C++ interface of the <a href="#">Task</a> kernel object, see <a href="#">Task</a> for the C interface	1391
<a href="#">L4::Thread</a>	
C++ <a href="#">L4</a> kernel thread interface, see <a href="#">Thread</a> for the C interface	1404
<a href="#">L4::Thread::Attr</a>	
<a href="#">Thread</a> attributes used for <a href="#">control()</a>	1419
<a href="#">L4::Thread::Modify_senders</a>	
Class wrapping a list of rules which modify the sender label of IPC messages inbound to this thread	1425
<a href="#">L4::Thread_group</a>	
C++ <a href="#">L4</a> kernel thread group interface, see <a href="#">Thread groups</a> for the C interface	1427
<a href="#">L4::Triggerable</a>	
Interface that allows an object to be triggered by some source	1431
<a href="#">L4::Type_info</a>	
Dynamic Type Information for <a href="#">L4Re</a> Interfaces	1435
<a href="#">L4::Type_info::Demand</a>	
Data type for expressing the needed receive buffers at the server-side of an interface	1436
<a href="#">L4::Type_info::Demand_t&lt; CAPS, FLAGS, MEM, PORTS &gt;</a>	
Template type statically describing demand of receive buffers	1440
<a href="#">L4::Type_info::Demand_union_t&lt; D1, D2 &gt;</a>	
Template type statically describing the combination of two <a href="#">Demand</a> object	1443
<a href="#">L4::Typeid::Detail::_Rpc&lt; OPCODE, O, X &gt;</a>	
Empty list of RPCs	1447
<a href="#">L4::Typeid::Detail::_Rpc&lt; OPCODE, O, Default_op&lt; R &gt; &gt;::Rpc&lt; Y &gt;</a>	
Find the given RPC in the list	1448
<a href="#">L4::Typeid::Detail::_Rpc&lt; OPCODE, O, R, X... &gt;</a>	
Non-empty list of RPCs	1448
<a href="#">L4::Typeid::Detail::_Rpc&lt; OPCODE, O, R, X... &gt;::Rpc&lt; Y &gt;</a>	
Find the given RPC in the list	1451
<a href="#">L4::Typeid::Detail::Rpc_end</a>	
Internal end-of-list marker	1452
<a href="#">L4::Typeid::P_dispatch&lt; LIST &gt;</a>	
Use for protocol based dispatch stage	1452
<a href="#">L4::Typeid::Raw_ipc&lt; CLASS &gt;</a>	
RPCs list for passing raw incoming IPC to the server object	1453
<a href="#">L4::Typeid::Rpc_nocode&lt; OPERATION &gt;</a>	
List of RPCs of an interface using a single operation without an opcode	1455
<a href="#">L4::Typeid::Rpc&lt; RPCS &gt;</a>	
Standard list of RPCs of an interface	1457
<a href="#">L4::Typeid::Rpc_code&lt; OPCODE_TYPE &gt;</a>	
List of RPCs of an interface using a special opcode type	1459
<a href="#">L4::Typeid::Rpc_code&lt; OPCODE_TYPE &gt;::F&lt; RPCS &gt;</a>	
	1460
<a href="#">L4::Typeid::Rpc_sys&lt; ARG &gt;</a>	
List of RPCs typically used for kernel interfaces	1463
<a href="#">L4::Types::__Add_rvalue_reference_helper&lt; T, typename &gt;</a>	
Helper template for <a href="#">Add_rvalue_reference</a>	1465
<a href="#">L4::Types::__Add_rvalue_reference_helper&lt; T, Void&lt; T &amp;&amp; &gt; &gt;</a>	
Helper template for <a href="#">Add_rvalue_reference</a>	1466
<a href="#">L4::Types::__Underlying_type_helper&lt; T, bool &gt;</a>	
Helper template for <a href="#">Underlying_type</a>	1468
<a href="#">L4::Types::__Underlying_type_helper&lt; T, false &gt;</a>	
Helper template for <a href="#">Underlying_type</a>	1469

<a href="#">L4::Types::Add_rvalue_reference&lt; T &gt;</a>	1471
Create an rvalue reference of the given type . . . . .	
<a href="#">L4::Types::Bool&lt; V &gt;</a>	1472
Boolean meta type . . . . .	
<a href="#">L4::Types::False</a>	1473
False meta value . . . . .	
<a href="#">L4::Types::Flags&lt; BITS_ENUM, UNDERLYING &gt;</a>	1476
Template for defining typical <a href="#">Flags</a> bitmaps . . . . .	
<a href="#">L4::Types::Flags_ops_t&lt; DT &gt;</a>	1480
Mixin class to define a set of friend bitwise operators on DT . . . . .	
<a href="#">L4::Types::Flags_t&lt; DT, T &gt;</a>	1483
Template type to define a flags type with bitwise operations . . . . .	
<a href="#">L4::Types::Int_for_size&lt; SIZE, bool &gt;</a>	1487
Metafunction to get an unsigned integral type for the given size . . . . .	
<a href="#">L4::Types::Int_for_type&lt; T &gt;</a>	1488
Metafunction to get an integral type of the same size as T . . . . .	
<a href="#">L4::Types::Integral_constant&lt; T, Value &gt;</a>	1489
Wrapper for a static constant of the given type . . . . .	
<a href="#">L4::Types::Is_enum&lt; T &gt;</a>	1490
Check whether the given type is an enumeration type . . . . .	
<a href="#">L4::Types::Same&lt; A, B &gt;</a>	1492
Compare two data types for equality . . . . .	
<a href="#">L4::Types::True</a>	1494
True meta value . . . . .	
<a href="#">L4::Types::Underlying_type&lt; T &gt;</a>	1497
Get an underlying type of an enumeration type . . . . .	
<a href="#">L4::Uart</a>	1498
Uart driver abstraction . . . . .	
<a href="#">L4::Uart_apb</a>	1505
Driver for the Advanced Peripheral Bus (APB) UART from the Cortex-M System Design Kit (CMSDK) . . . . .	
<a href="#">L4::Unknown_error</a>	1510
Exception for an unknown condition . . . . .	
<a href="#">L4::Vcon</a>	1513
C++ <a href="#">L4 Vcon</a> interface, see <a href="#">Virtual Console</a> for the C interface . . . . .	
<a href="#">L4::Vm</a>	1523
Virtual machine host address space . . . . .	
<a href="#">l4_buf_regs_t</a>	1527
Encapsulation of the buffer-registers block in the UTCB . . . . .	
<a href="#">l4_exc_regs_t</a>	1528
UTCB structure for exceptions . . . . .	
<a href="#">l4_fpage_t</a>	1531
L4 flexpage type . . . . .	
<a href="#">l4_icu_info_t</a>	1532
Info structure for an ICU . . . . .	
<a href="#">l4_icu_msi_info_t</a>	1533
Info to use for a specific MSI . . . . .	
<a href="#">l4_kernel_info_mem_desc_t</a>	1534
Memory descriptor data structure . . . . .	
<a href="#">l4_kernel_info_t</a>	1535
L4 Kernel Interface Page . . . . .	
<a href="#">l4_msg_regs_t</a>	1536
Encapsulation of the message-register block in the UTCB . . . . .	
<a href="#">l4_msgtag_t</a>	1537
Message tag data structure . . . . .	
<a href="#">l4_sched_cpu_set_t</a>	1540
CPU sets . . . . .	

<a href="#">l4_sched_param_t</a>	Scheduler parameter set . . . . .	1544
<a href="#">l4_snd_fpage_t</a>	Send-flexpage types . . . . .	1545
<a href="#">l4_thread_regs_t</a>	Encapsulation of the thread-control-register block of the UTCB . . . . .	1546
<a href="#">l4_timeout_s</a>	Basic timeout specification . . . . .	1547
<a href="#">l4_timeout_t</a>	Timeout pair . . . . .	1548
<a href="#">l4_vcon_attr_t</a>	Vcon attribute structure . . . . .	1549
<a href="#">l4_vcpu_arch_state_t</a>	Architecture-specific vCPU state . . . . .	1551
<a href="#">l4_vcpu_ipc_regs_t</a>	vCPU message registers . . . . .	1551
<a href="#">l4_vcpu_regs_t</a>	vCPU registers . . . . .	1553
<a href="#">l4_vcpu_state_t</a>	State of a vCPU . . . . .	1556
<a href="#">l4_vm_svm_vmcb_control_area</a>	VMCB structure for SVM VMs . . . . .	1560
<a href="#">l4_vm_svm_vmcb_state_save_area</a>	State save area structure for SVM VMs . . . . .	1560
<a href="#">l4_vm_svm_vmcb_state_save_area_seg</a>	State save area segment selector struct . . . . .	1562
<a href="#">l4_vm_svm_vmcb_t</a>	Control structure for SVM VMs . . . . .	1562
<a href="#">l4_vm_tz_state</a>	State structure for TrustZone VMs . . . . .	1564
<a href="#">l4_vm_vmx_vcpu_infos_t</a>	VMX information members . . . . .	1564
<a href="#">l4_vm_vmx_vcpu_state_t</a>	VMX vCPU state . . . . .	1565
<a href="#">l4_vm_vmx_vcpu_vmcs_t</a>	VMX software VMCS . . . . .	1567
<a href="#">l4_vmx_offset_table_t</a>	Software VMCS field offset table . . . . .	1568
<a href="#">L4drivers::Mmio_register_block&lt; MAX_BITS &gt;</a>	An MMIO block with up to 64-bit register access (32-bit default) and little endian byte order . . . . .	1570
<a href="#">L4drivers::Register_block&lt; MAX_BITS, BLOCK &gt;</a>	Handles a reference to a register block of the given maximum access width . . . . .	1572
<a href="#">L4drivers::Register_block_base&lt; MAX_BITS &gt;</a>	Abstract register block interface . . . . .	1576
<a href="#">L4drivers::Register_block_impl&lt; BASE, MAX_BITS &gt;</a>	Implementation helper for register blocks . . . . .	1577
<a href="#">L4drivers::Register_block_tmpl&lt; BLOCK &gt;</a>	Helper template that translates to the <a href="#">Register_block_base</a> interface . . . . .	1579
<a href="#">L4drivers::Register_tmpl&lt; BITS, BLOCK &gt;</a>	Single hardware register inside a <a href="#">Register_block_base</a> interface . . . . .	1580
<a href="#">L4drivers::Ro_register_block&lt; MAX_BITS, BLOCK &gt;</a>	Handles a reference to a read only register block of the given maximum access width . . . . .	1586
<a href="#">L4drivers::Ro_register_tmpl&lt; BITS, BLOCK &gt;</a>	Single read only register inside a <a href="#">Register_block_base</a> interface . . . . .	1588
<a href="#">L4Re::Cap_alloc</a>	Capability allocator interface . . . . .	1591
<a href="#">L4Re::Console</a>	<a href="#">Console</a> class . . . . .	1594

<a href="#">L4Re::Core::Ref_ptr&lt; T, CNT &gt;</a>	
A reference-counting pointer with automatic cleanup	1597
<a href="#">L4Re::Dataspace</a>	
Interface for memory-like objects	1602
<a href="#">L4Re::Dataspace::F</a>	
<a href="#">Dataspace</a> flags definitions	1615
<a href="#">L4Re::Dataspace::Stats</a>	
Information about the dataspace	1616
<a href="#">L4Re::Debug_obj</a>	
Debug interface	1617
<a href="#">L4Re::Default_event_payload</a>	
Default event stream payload	1621
<a href="#">L4Re::Dma_space</a>	
Managed DMA Address Space	1622
<a href="#">L4Re::Env</a>	
C++ interface of the initial environment that is provided to an <a href="#">L4</a> task	1629
<a href="#">L4Re::Event</a>	
<a href="#">Event</a> class	1644
<a href="#">L4Re::Event_buffer_t&lt; PAYLOAD &gt;</a>	
<a href="#">Event</a> buffer class	1654
<a href="#">L4Re::Event_buffer_t&lt; PAYLOAD &gt;::Event</a>	
<a href="#">Event</a> structure used in buffer	1658
<a href="#">L4Re::Inhibitor</a>	
Set of inhibitor locks, which inhibit specific actions when held	1659
<a href="#">L4Re::Itas</a>	
Interface to the ITAS	1665
<a href="#">L4Re::Log</a>	
<a href="#">Log</a> interface class	1675
<a href="#">L4Re::Mem_alloc</a>	
Memory allocation interface	1681
<a href="#">L4Re::Mem_alloc::Stats</a>	
Statistics about memory-allocator	1687
<a href="#">L4Re::Mmio_space</a>	
Interface for memory-like address space accessible via IPC	1690
<a href="#">L4Re::Namespace</a>	
Name-space interface	1695
<a href="#">L4Re::Ned::Cmd_control</a>	
Direct control interface for Ned	1705
<a href="#">L4Re::Parent</a>	
<a href="#">Parent</a> interface	1707
<a href="#">L4Re::Random</a>	
Low-bandwidth interface for random number generators	1712
<a href="#">L4Re::Rm</a>	
<a href="#">Region</a> map	1716
<a href="#">L4Re::Rm::Area</a>	
An area is a range of virtual addresses which is reserved, see <a href="#">L4Re::Rm::reserve_area()</a>	1737
<a href="#">L4Re::Rm::F</a>	
<a href="#">Rm</a> flags definitions	1737
<a href="#">L4Re::Rm::Region</a>	
A region is a range of virtual addresses which is backed by content	1739
<a href="#">L4Re::Rm::Unique_region&lt; T &gt;</a>	
Unique region	1740
<a href="#">L4Re::Smart_cap_auto&lt; Unmap_flags &gt;</a>	
Helper for <a href="#">Unique_cap</a> and <a href="#">Unique_del_cap</a>	1746
<a href="#">L4Re::Smart_count_cap&lt; Unmap_flags &gt;</a>	
Helper for <a href="#">Ref_cap</a> and <a href="#">Ref_del_cap</a>	1746
<a href="#">L4Re::Util::Cap_alloc</a>	
Adapter to expose the cap allocator implementation as <a href="#">L4Re::Cap_alloc</a> compatible class	1748

<a href="#">L4Re::Util::Bitmap&lt; BITS &gt;</a>	
A static bitmap	1751
<a href="#">L4Re::Util::Bitmap_base</a>	
Basic bitmap abstraction	1756
<a href="#">L4Re::Util::Bitmap_base::Bit</a>	
A writable bit in a bitmap	1764
<a href="#">L4Re::Util::Bitmap_base::Char&lt; BITS &gt;</a>	
Helper abstraction for a byte contained in the bitmap	1764
<a href="#">L4Re::Util::Bitmap_base::Word&lt; BITS &gt;</a>	
Helper abstraction for a word contained in the bitmap	1765
<a href="#">L4Re::Util::Br_manager</a>	
Buffer-register (BR) manager for <a href="#">L4::Server</a>	1766
<a href="#">L4Re::Util::Br_manager_hooks</a>	
Predefined server-loop hooks for a server loop using the <a href="#">Br_manager</a>	1772
<a href="#">L4Re::Util::Br_manager_timeout_hooks</a>	
Predefined server-loop hooks for a server with using the <a href="#">Br_manager</a> and a timeout queue	1774
<a href="#">L4Re::Util::Cap_alloc_base</a>	
Capability allocator	1778
<a href="#">L4Re::Util::Counter&lt; COUNTER &gt;</a>	
Counter for <a href="#">Counting_cap_alloc</a> with variable data width	1779
<a href="#">L4Re::Util::Counter_atomic&lt; COUNTER &gt;</a>	
Thread safe version of counter for <a href="#">Counting_cap_alloc</a>	1780
<a href="#">L4Re::Util::Counting_cap_alloc&lt; COUNTERTYPE, Dbg &gt;</a>	
Internal reference-counting cap allocator	1782
<a href="#">L4Re::Util::Dataspace_svr</a>	
Dataspace server class	1788
<a href="#">L4Re::Util::Event_buffer_consumer_t&lt; PAYLOAD &gt;</a>	
An event buffer consumer	1795
<a href="#">L4Re::Util::Event_buffer_t&lt; PAYLOAD &gt;</a>	
Event_buffer utility class	1798
<a href="#">L4Re::Util::Event_svr&lt; SVR &gt;</a>	
Convenience wrapper for implementing an event server	1802
<a href="#">L4Re::Util::Event_t&lt; PAYLOAD &gt;</a>	
Convenience wrapper for getting access to an event object	1804
<a href="#">L4Re::Util::Item_alloc_base</a>	
Item allocator	1808
<a href="#">L4Re::Util::Names::Name</a>	
Name class	1809
<a href="#">L4Re::Util::Names::Name_space</a>	
Abstract server-side implementation of the <a href="#">L4::Namespace</a> interface	1812
<a href="#">L4Re::Util::Object_registry</a>	
A registry that manages server objects and their attached IPC gates for a single server loop for a specific thread	1817
<a href="#">L4Re::Util::Ref_cap&lt; T &gt;</a>	
Automatic capability that implements automatic free and unmap of the capability selector	1824
<a href="#">L4Re::Util::Ref_del_cap&lt; T &gt;</a>	
Automatic capability that implements automatic free and unmap+delete of the capability selector	1826
<a href="#">L4Re::Util::Registry_server&lt; LOOP_HOOKS &gt;</a>	
A server loop object which has a <a href="#">Object_registry</a> included	1827
<a href="#">L4Re::Util::Smart_cap_auto&lt; Unmap_flags &gt;</a>	
Helper for <a href="#">Unique_cap</a> and <a href="#">Unique_del_cap</a>	1833
<a href="#">L4Re::Util::Smart_count_cap&lt; Unmap_flags &gt;</a>	
Helper for <a href="#">Ref_cap</a> and <a href="#">Ref_del_cap</a>	1834
<a href="#">L4Re::Util::Vcon_svr&lt; SVR &gt;</a>	
Console server template class	1835
<a href="#">L4Re::Util::Video::Goos_svr</a>	
Goos server class	1836

<a href="#">L4Re::Vfs::Be_file</a>	Boiler plate class for implementing an open file for <a href="#">L4Re::Vfs</a>	1840
<a href="#">L4Re::Vfs::Be_file_system</a>	Boilerplate class for implementing a <a href="#">L4Re::Vfs::File_system</a>	1845
<a href="#">L4Re::Vfs::Directory</a>	Interface for a POSIX file that is a directory	1848
<a href="#">L4Re::Vfs::File</a>	The basic interface for an open POSIX file	1853
<a href="#">L4Re::Vfs::File_system</a>	Basic interface for an <a href="#">L4Re::Vfs</a> file system	1857
<a href="#">L4Re::Vfs::Fs</a>	POSIX File-system related functionality	1859
<a href="#">L4Re::Vfs::Generic_file</a>	The common interface for an open POSIX file	1864
<a href="#">L4Re::Vfs::Mman</a>	Interface for POSIX memory management	1873
<a href="#">L4Re::Vfs::Ops</a>	Interface for the POSIX backends of an application	1874
<a href="#">L4Re::Vfs::Regular_file</a>	Interface for a POSIX file that provides regular file semantics	1877
<a href="#">L4Re::Vfs::Special_file</a>	Interface for a POSIX file that provides special file semantics	1887
<a href="#">L4Re::Video::Color_component</a>	A color component	1890
<a href="#">L4Re::Video::Goos</a>	Class that abstracts framebuffers	1895
<a href="#">L4Re::Video::Goos::Info</a>	Information structure of a <a href="#">Goos</a>	1905
<a href="#">L4Re::Video::Pixel_info</a>	Pixel information	1907
<a href="#">L4Re::Video::View</a>	View of a framebuffer	1918
<a href="#">L4Re::Video::View::Info</a>	Information structure of a view	1925
<a href="#">l4re_aux_t</a>	Auxiliary descriptor	1927
<a href="#">l4re_ds_stats_t</a>	Information about the data space	1928
<a href="#">l4re_elf_aux_mword_t</a>	Auxiliary vector element for a single unsigned data word	1928
<a href="#">l4re_elf_aux_t</a>	Generic header for each auxiliary vector element	1929
<a href="#">l4re_elf_aux_vma_t</a>	Auxiliary vector element for a reserved virtual memory area	1930
<a href="#">l4re_env_cap_entry_t</a>	Entry in the <a href="#">L4Re</a> environment array for the named initial objects	1930
<a href="#">l4re_env_t</a>	Initial environment data structure	1932
<a href="#">l4re_event_t</a>	Event structure used in buffer	1935
<a href="#">l4re_video_color_component_t</a>	Color component structure	1936
<a href="#">l4re_video_goos_info_t</a>	Goos information structure	1936
<a href="#">l4re_video_pixel_info_t</a>	Pixel_info structure	1938
<a href="#">l4re_video_view_info_t</a>	View information structure	1939

<a href="#">l4re_video_view_t</a>	
C representation of a goos view	1941
<a href="#">l4shmc_ringbuf_head_t</a>	
Head field of a ring buffer	1942
<a href="#">l4shmc_ringbuf_t</a>	
Ring buffer	1943
<a href="#">l4util_l4mod_info</a>	
Base module structure	1944
<a href="#">l4util_l4mod_mod</a>	
A single module	1946
<a href="#">l4util_mb_addr_range_t</a>	
INT-15, AX=E820 style "AddressRangeDescriptor" ...with a "size" parameter on the front which is the structure size - 4, pointing to the next one, up until the full buffer length of the memory map has been reached	1947
<a href="#">l4util_mb_apm_t</a>	
APM BIOS info	1948
<a href="#">l4util_mb_drive_t</a>	
Drive Info structure	1948
<a href="#">l4util_mb_info_t</a>	
MultiBoot Info description	1949
<a href="#">l4util_mb_mod_t</a>	
The structure type "mod_list" is used by the <a href="#">multiboot_info</a> structure	1951
<a href="#">l4util_mb_vbe_ctrl_t</a>	
VBE controller information	1952
<a href="#">l4util_mb_vbe_mode_t</a>	
VBE mode information	1952
<a href="#">L4vbus::Device</a>	
Device on a <a href="#">L4vbus::Vbus</a>	1956
<a href="#">L4vbus::Gpio_module</a>	
A <a href="#">Gpio_module</a> groups multiple GPIO pins together	1966
<a href="#">L4vbus::Gpio_module::Pin_slice</a>	
A slice of the pins provided by this module	1973
<a href="#">L4vbus::Gpio_pin</a>	
A GPIO pin	1973
<a href="#">L4vbus::Icu</a>	
Vbus Interrupt controller API	1982
<a href="#">L4vbus::Pci_dev</a>	
A PCI device	1986
<a href="#">L4vbus::Pci_host_bridge</a>	
A Pci host bridge	1992
<a href="#">L4vbus::Pm&lt; DEC &gt;</a>	
Power-management API mixin	1998
<a href="#">L4vbus::Vbus</a>	
The virtual bus ( <a href="#">Vbus</a> ) interface	2001
<a href="#">l4vbus_device_t</a>	
Detailed information about a vbus device	2012
<a href="#">l4vbus_resource_t</a>	
Description of a single vbus resource	2013
<a href="#">L4vcpu::State</a>	
C++ implementation of state word in the vCPU area	2014
<a href="#">L4vcpu::Vcpu</a>	
C++ implementation of the vCPU save state area	2016
<a href="#">L4virtio::Device</a>	
IPC interface for virtio over <a href="#">L4 IPC</a>	2029
<a href="#">L4virtio::Driver::Block_device</a>	
Simple class for accessing a virtio block device synchronously	2039
<a href="#">L4virtio::Driver::Block_device::Handle</a>	
Handle to an ongoing request	2047



<a href="#">L4virtio::Driver::Device</a>	Client-side implementation for a general virtio device . . . . .	2047
<a href="#">L4virtio::Driver::Virtio_net_device</a>	Simple class for accessing a virtio net device . . . . .	2060
<a href="#">L4virtio::Driver::Virtio_net_device::Packet</a>	Structure for a network packet (header including data) with maximum size, assuming that no extra features have been negotiated . . . . .	2069
<a href="#">L4virtio::Driver::Virtqueue</a>	Driver-side implementation of a <a href="#">Virtqueue</a> . . . . .	2070
<a href="#">L4virtio::Ptr&lt; T &gt;</a>	Pointer used in virtio descriptors . . . . .	2079
<a href="#">L4virtio::Svr::Bad_descriptor</a>	Exception used by Queue to indicate descriptor errors . . . . .	2082
<a href="#">L4virtio::Svr::Block_dev_base&lt; Ds_data &gt;</a>	Base class for virtio block devices . . . . .	2084
<a href="#">L4virtio::Svr::Block_request&lt; Ds_data &gt;</a>	A request to read or write data . . . . .	2093
<a href="#">L4virtio::Svr::Console::Control_message</a>	Virtio console control message . . . . .	2095
<a href="#">L4virtio::Svr::Console::Control_request</a>	Specialised <a href="#">Virtqueue::Request</a> providing access to control message payload . . . . .	2097
<a href="#">L4virtio::Svr::Console::Device</a>	Base class implementing a virtio console device with L4Re-based notification handling . . . . .	2098
<a href="#">L4virtio::Svr::Console::Device_port</a>	A console port with associated read/write state . . . . .	2112
<a href="#">L4virtio::Svr::Console::Features</a>	Virtio console specific feature bits . . . . .	2116
<a href="#">L4virtio::Svr::Console::Port</a>	Representation of a Virtio console port . . . . .	2121
<a href="#">L4virtio::Svr::Console::Port::Transition</a>	State transition from last report state to current state . . . . .	2125
<a href="#">L4virtio::Svr::Console::Virtio_con</a>	Base class implementing a virtio console functionality . . . . .	2126
<a href="#">L4virtio::Svr::Data_buffer</a>	Abstract data buffer . . . . .	2143
<a href="#">L4virtio::Svr::Dev_config</a>	Abstraction for L4-Virtio device config memory . . . . .	2147
<a href="#">L4virtio::Svr::Dev_features</a>	Type for device feature bitmap . . . . .	2159
<a href="#">L4virtio::Svr::Dev_status</a>	Type of the device status register . . . . .	2162
<a href="#">L4virtio::Svr::Device_t&lt; DATA &gt;</a>	Server-side L4-VIRTIO device stub . . . . .	2165
<a href="#">L4virtio::Svr::Driver_mem_list_t&lt; DATA &gt;</a>	List of driver memory regions assigned to a single L4-VIRTIO transport instance . . . . .	2172
<a href="#">L4virtio::Svr::Driver_mem_region_t&lt; DATA &gt;</a>	Region of driver memory, that shall be managed locally . . . . .	2178
<a href="#">L4virtio::Svr::Request_processor</a>	Encapsulate the state for processing a VIRTIO request . . . . .	2185
<a href="#">L4virtio::Svr::Scmi::Base_attr_t</a>	SCMI base protocol attributes . . . . .	2192
<a href="#">L4virtio::Svr::Scmi::Base_proto</a>	Base class for the SCMI base protocol . . . . .	2193
<a href="#">L4virtio::Svr::Scmi::Perf_proto</a>	Base class for the SCMI performance protocol . . . . .	2195
<a href="#">L4virtio::Svr::Scmi::Performance_attr_t</a>	SCMI performance protocol attributes . . . . .	2198

<a href="#">L4virtio::Svr::Scmi::Performance_describe_level_t</a>	
SCMI performance describe level	2199
<a href="#">L4virtio::Svr::Scmi::Performance_describe_levels_n_t</a>	
SCMI performance describe levels numbers	2199
<a href="#">L4virtio::Svr::Scmi::Performance_domain_attr_t</a>	
SCMI performance domain protocol attributes	2201
<a href="#">L4virtio::Svr::Scmi::Proto&lt; OBSERV &gt;</a>	
Base class for all protocols	2203
<a href="#">L4virtio::Svr::Scmi::Scmi_dev</a>	
A server implementation of the virtio-scmi protocol	2204
<a href="#">L4virtio::Svr::Scmi::Scmi_hdr_t</a>	
SCMI header	2208
<a href="#">L4virtio::Svr::Virtio_gpio&lt; Request_handler, Epiface &gt;</a>	
A server implementation of the virtio-gpio protocol	2210
<a href="#">L4virtio::Svr::Virtio_gpio&lt; Request_handler, Epiface &gt;::Host_irq</a>	
Handler for the host irq	2214
<a href="#">L4virtio::Svr::Virtio_gpio&lt; Request_handler, Epiface &gt;::Irq_handler</a>	
Handler for an gpio pin irq	2218
<a href="#">L4virtio::Svr::Virtio_gpio&lt; Request_handler, Epiface &gt;::Request_processor</a>	
Generic handler for the Virtio requests	2219
<a href="#">L4virtio::Svr::Virtio_i2c&lt; Request_handler, Epiface &gt;</a>	
A server implementation of the virtio-i2c protocol	2222
<a href="#">L4virtio::Svr::Virtio_i2c&lt; Request_handler, Epiface &gt;::Host_irq</a>	
Handler for the host irq	2226
<a href="#">L4virtio::Svr::Virtio_i2c&lt; Request_handler, Epiface &gt;::Request_processor</a>	
Handler for the Virtio requests	2230
<a href="#">L4virtio::Svr::Virtio_rng&lt; Rnd_state, Epiface &gt;</a>	
A server implementation of the virtio-rng protocol	2233
<a href="#">L4virtio::Svr::Virtio_rng&lt; Rnd_state, Epiface &gt;::Host_irq</a>	
Handler for the host irq	2237
<a href="#">L4virtio::Svr::Virtio_rng&lt; Rnd_state, Epiface &gt;::Request_processor</a>	
Handler for the Virtio requests	2241
<a href="#">L4virtio::Svr::Virtio_spi&lt; Spi_request_handler, Epiface &gt;</a>	
A server implementation of the virtio-spi protocol	2243
<a href="#">L4virtio::Svr::Virtio_spi&lt; Spi_request_handler, Epiface &gt;::Host_irq</a>	
Handler for the host IRQ	2248
<a href="#">L4virtio::Svr::Virtio_spi&lt; Spi_request_handler, Epiface &gt;::Request_processor</a>	
Handler for the Virtio requests	2252
<a href="#">L4virtio::Svr::Virtqueue</a>	
Virtqueue implementation for the device	2255
<a href="#">L4virtio::Svr::Virtqueue::Head_desc</a>	
VIRTIO request, essentially a descriptor from the available ring	2267
<a href="#">L4virtio::Virtqueue</a>	
Low-level Virtqueue	2270
<a href="#">L4virtio::Virtqueue::Avail</a>	
Type of available ring, this is read-only for the host	2287
<a href="#">L4virtio::Virtqueue::Avail::Flags</a>	
Flags of the available ring	2288
<a href="#">L4virtio::Virtqueue::Desc</a>	
Descriptor in the descriptor table	2289
<a href="#">L4virtio::Virtqueue::Desc::Flags</a>	
Type for descriptor flags	2291
<a href="#">L4virtio::Virtqueue::Used</a>	
Used ring	2293
<a href="#">L4virtio::Virtqueue::Used::Flags</a>	
Flags for the used ring	2294
<a href="#">L4virtio::Virtqueue::Used_elem</a>	
Type of an element of the used ring	2296

<a href="#">l4virtio_block_config_t</a>	Device configuration for block devices . . . . .	2297
<a href="#">l4virtio_block_discard_t</a>	Structure used for the write zeroes and discard commands . . . . .	2298
<a href="#">l4virtio_block_header_t</a>	Header structure of a request for a block device . . . . .	2299
<a href="#">l4virtio_config_hdr_t</a>	L4-VIRTIO config header, provided in shared data space . . . . .	2300
<a href="#">l4virtio_config_queue_t</a>	Queue configuration entry . . . . .	2301
<a href="#">l4virtio_input_absinfo_t</a>	Information about the absolute axis in the underlying evdev implementation . . . . .	2302
<a href="#">l4virtio_input_config_t</a>	Device configuration for input devices . . . . .	2303
<a href="#">l4virtio_input_devids_t</a>	Device ID information for the device . . . . .	2303
<a href="#">l4virtio_input_event_t</a>	Single event in event or status queue . . . . .	2304
<a href="#">l4virtio_net_config_t</a>	Device configuration for network devices . . . . .	2305
<a href="#">l4virtio_net_header_t</a>	Header structure of a request for a network device . . . . .	2305
<a href="#">L4virtio_port</a>	A Port on the Virtio Net Switch . . . . .	2306
<a href="#">Mac_addr</a>	A wrapper class around the value of a MAC address . . . . .	2312
<a href="#">Mac_table&lt; Size &gt;</a>	<a href="#">Mac_table</a> manages a 1:n association between ports and MAC addresses . . . . .	2312
<a href="#">Net_transfer</a>	A network request to only a single destination . . . . .	2315
<a href="#">Rm</a>	<a href="#">Region</a> map . . . . .	2318
<a href="#">Rm::Area</a>	An area is a range of virtual addresses which is reserved, see <a href="#">L4Re::Rm::reserve_area()</a> . . . . .	2332
<a href="#">Rm::F</a>	<a href="#">Rm</a> flags definitions . . . . .	2333
<a href="#">Rm::Region</a>	A region is a range of virtual addresses which is backed by content . . . . .	2335
<a href="#">Rm::Unique_region&lt; T &gt;</a>	Unique region . . . . .	2336
<a href="#">Switch_factory</a>	The IPC interface for creating ports . . . . .	2341
<a href="#">Virtio_net</a>	The Base class of a Port . . . . .	2345
<a href="#">Virtio_net_request</a>	Abstraction for a network request . . . . .	2350
<a href="#">Virtio_switch</a>	The Virtio switch contains all ports and processes network requests . . . . .	2353
<a href="#">Virtio_vlan_mangle</a>	Class for VLAN packet rewriting . . . . .	2358



# Chapter 12

## File Index

### 12.1 File List

Here is a list of all documented files with brief descriptions:

pkg/drivers-frst/include/asm_access_gen.h . . . . .	2368
pkg/drivers-frst/include/hw_mmio_register_block . . . . .	2369
pkg/drivers-frst/include/hw_register_block . . . . .	2370
pkg/drivers-frst/include/io_regblock.h . . . . .	2373
pkg/drivers-frst/include/io_regblock_port.h . . . . .	2375
pkg/drivers-frst/include/Makefile . . . . .	2419
pkg/drivers-frst/include/poll_timeout_counter.h . . . . .	2376
pkg/drivers-frst/include/ARCH-amd64/asm_access.h . . . . .	2363
pkg/drivers-frst/include/ARCH-arm/asm_access.h . . . . .	2364
pkg/drivers-frst/include/ARCH-arm64/asm_access.h . . . . .	2365
pkg/drivers-frst/include/ARCH-mips/asm_access.h . . . . .	2366
pkg/drivers-frst/include/ARCH-ppc32/asm_access.h . . . . .	2366
pkg/drivers-frst/include/ARCH-riscv/asm_access.h . . . . .	2366
pkg/drivers-frst/include/ARCH-sparc/asm_access.h . . . . .	2367
pkg/drivers-frst/include/ARCH-x86/asm_access.h . . . . .	2368
pkg/drivers-frst/uart/include/device.h . . . . .	2377
pkg/drivers-frst/uart/include/Makefile . . . . .	2419
pkg/drivers-frst/uart/include/uart_16550.h . . . . .	2378
pkg/drivers-frst/uart/include/uart_16550_dw.h . . . . .	2379
pkg/drivers-frst/uart/include/uart_apb.h . . . . .	2380
pkg/drivers-frst/uart/include/uart_base.h . . . . .	2380
pkg/drivers-frst/uart/include/uart_cadence.h . . . . .	2382
pkg/drivers-frst/uart/include/uart_dcc-v6.h . . . . .	2382
pkg/drivers-frst/uart/include/uart_dm.h . . . . .	2383
pkg/drivers-frst/uart/include/uart_dummy.h . . . . .	2383
pkg/drivers-frst/uart/include/uart_geni.h . . . . .	2384
pkg/drivers-frst/uart/include/uart_imx.h . . . . .	2384
pkg/drivers-frst/uart/include/uart_leon3.h . . . . .	2385
pkg/drivers-frst/uart/include/uart_linfex.h . . . . .	2386
pkg/drivers-frst/uart/include/uart_lpuart.h . . . . .	2386
pkg/drivers-frst/uart/include/uart_mvebu.h . . . . .	2387
pkg/drivers-frst/uart/include/uart_of.h . . . . .	2387
pkg/drivers-frst/uart/include/uart_omap35x.h . . . . .	2388
pkg/drivers-frst/uart/include/uart_pl011.h . . . . .	2388
pkg/drivers-frst/uart/include/uart_s3c2410.h . . . . .	2389

pkg/drivers-frst/uart/include/uart_sa1000.h	2390
pkg/drivers-frst/uart/include/uart_sbi.h	2391
pkg/drivers-frst/uart/include/uart_sh.h	2391
pkg/drivers-frst/uart/include/uart_sifive.h	2392
pkg/drivers-frst/uart/include/uart_tegra-tcu.h	2392
pkg/l4re-core/ned/doc/tutorial.lua	2393
pkg/l4re-core/ned/lib/include/cmd_control	2395
pkg/l4re-core/ned/lib/include/Makefile	2419
pkg/uvmm/configs/vmm.lua	2396
pkg/virtio-net-switch/server/switch/debug.h	2404
pkg/virtio-net-switch/server/switch/filter.cc	2407
pkg/virtio-net-switch/server/switch/filter.h	2407
pkg/virtio-net-switch/server/switch/mac_addr.h	2408
pkg/virtio-net-switch/server/switch/mac_table.h	2409
pkg/virtio-net-switch/server/switch/main.cc	2410
pkg/virtio-net-switch/server/switch/Makefile	2419
pkg/virtio-net-switch/server/switch/options.cc	2419
pkg/virtio-net-switch/server/switch/options.h	2422
pkg/virtio-net-switch/server/switch/port.h	2422
pkg/virtio-net-switch/server/switch/port_ixl.h	2425
pkg/virtio-net-switch/server/switch/port_l4virtio.h	2427
pkg/virtio-net-switch/server/switch/request.h	2430
pkg/virtio-net-switch/server/switch/request_ixl.h	2432
pkg/virtio-net-switch/server/switch/request_l4virtio.h	2433
pkg/virtio-net-switch/server/switch/stats.h	2436
pkg/virtio-net-switch/server/switch/switch.cc	2437
pkg/virtio-net-switch/server/switch/switch.h	2440
pkg/virtio-net-switch/server/switch/virtio_net.h	2441
pkg/virtio-net-switch/server/switch/virtio_net_buffer.h	2445
pkg/virtio-net-switch/server/switch/vlan.h	2446
amd64/l4/sys/__kip-arch.h	2487
amd64/l4/sys/__vcpu-arch.h	
AMD64-specific vCPU interface	2488
amd64/l4/sys/ktrace_events.h	2500
amd64/l4/sys/linkage.h	
Linkage	2512
amd64/l4/sys/segment.h	
Segment handling (AMD64)	2447
amd64/l4/sys/vm.h	2518
amd64/l4/sys/arch/cache.h	
Cache functions	3037
amd64/l4/sys/arch/consts.h	
Common L4 constants, AMD64 version	3053
amd64/l4/sys/arch/ipc.h	3160
amd64/l4/sys/arch/kip.h	3342
amd64/l4/sys/arch/l4int.h	
Fixed sized integer types, AMD64 version	3205
amd64/l4/sys/arch/platform_control.h	3223
amd64/l4/sys/arch/task.h	3253
amd64/l4/sys/arch/thread.h	2524
amd64/l4/sys/arch/utcb.h	
UTCB definitions for AMD64	3274
amd64/l4/util/bitops_arch.h	
Amd64 bit manipulation functions	2538
amd64/l4/util/cpu.h	
CPU related functions	2546
amd64/l4/util/irq.h	
Some PIC and hardware interrupt related functions	2683

amd64/l4/util/ <a href="#">mbi_argv.h</a>	
Command line handling . . . . .	2551
amd64/l4/util/ <a href="#">perform.h</a>	
Performance Monitoring using P5/P6 Measurement Counters . . . . .	2456
amd64/l4/util/ <a href="#">port_io.h</a>	
X86 port I/O . . . . .	2468
amd64/l4/util/ <a href="#">rdtsc.h</a>	
Timestamp counter related functions . . . . .	2476
amd64/l4/util/ <a href="#">spin.h</a>	
Spinning for amd64 . . . . .	2485
amd64/l4/util/arch/ <a href="#">l4_macros.h</a>	
Main function . . . . .	2521
amd64/l4/util/arch/ <a href="#">thread.h</a>	2524
arm/l4/sys/ <a href="#">__kip-arch.h</a>	2487
arm/l4/sys/ <a href="#">__vcpu-arch.h</a>	
ARM-specific vCPU interface . . . . .	2491
arm/l4/sys/ <a href="#">atomic.h</a>	3304
arm/l4/sys/ <a href="#">ktrace_events.h</a>	2503
arm/l4/sys/ <a href="#">linkage.h</a>	
Linkage . . . . .	2513
arm/l4/sys/ <a href="#">mem_op.h</a>	
Memory access functions (ARM specific) . . . . .	2515
arm/l4/sys/ <a href="#">syscall_defs.h</a>	
Syscall entry definitions . . . . .	2517
arm/l4/sys/ <a href="#">vm.h</a>	
ARM virtualization interface . . . . .	2518
arm/l4/sys/arch/ <a href="#">cache.h</a>	
Cache functions . . . . .	3038
arm/l4/sys/arch/ <a href="#">consts.h</a>	
Common L4 constants, arm version . . . . .	3054
arm/l4/sys/arch/ <a href="#">ipc.h</a>	3161
arm/l4/sys/arch/ <a href="#">kip.h</a>	3343
arm/l4/sys/arch/ <a href="#">l4int.h</a>	
Fixed sized integer types, arm version . . . . .	3206
arm/l4/sys/arch/ <a href="#">platform_control.h</a>	3223
arm/l4/sys/arch/ <a href="#">task.h</a>	3253
arm/l4/sys/arch/ <a href="#">thread.h</a>	
ARM-specific thread related definitions . . . . .	2524
arm/l4/sys/arch/ <a href="#">utcb.h</a>	
UTCB definitions for ARM . . . . .	3276
arm/l4/util/ <a href="#">bitops_arch.h</a>	
ARM specific implementation of bitops functions . . . . .	2542
arm/l4/util/ <a href="#">cpu.h</a>	
CPU related functions . . . . .	2548
arm/l4/util/ <a href="#">irq.h</a>	
ARM specific implementation of irq functions . . . . .	2684
arm/l4/util/ <a href="#">mbi_argv.h</a>	
Multiboot . . . . .	2552
arm/l4/util/arch/ <a href="#">l4_macros.h</a>	
Main function . . . . .	2521
arm/l4/util/arch/ <a href="#">thread.h</a>	2525
amd64/l4/sys/ <a href="#">__kip-arch.h</a>	2488
amd64/l4/sys/ <a href="#">__vcpu-arch.h</a>	
ARM64-specific vCPU interface . . . . .	2494
amd64/l4/sys/ <a href="#">ktrace_events.h</a>	2506
amd64/l4/sys/ <a href="#">linkage.h</a>	2514
amd64/l4/sys/ <a href="#">vm.h</a>	2520

arm64/l4/sys/arch/ <a href="#">cache.h</a>	
Cache functions . . . . .	3040
arm64/l4/sys/arch/ <a href="#">consts.h</a>	
Common L4 constants, arm version . . . . .	3055
arm64/l4/sys/arch/ <a href="#">ipc.h</a> . . . . .	3161
arm64/l4/sys/arch/ <a href="#">kip.h</a> . . . . .	3343
arm64/l4/sys/arch/ <a href="#">l4int.h</a>	
Fixed sized integer types, arm version . . . . .	3207
arm64/l4/sys/arch/ <a href="#">platform_control.h</a> . . . . .	3224
arm64/l4/sys/arch/ <a href="#">task.h</a> . . . . .	3253
arm64/l4/sys/arch/ <a href="#">thread.h</a>	
ARM64-specific thread related definitions . . . . .	2525
arm64/l4/sys/arch/ <a href="#">utcb.h</a>	
UTCB definitions for ARM64 . . . . .	3279
contrib/libio-io/l4/io/ <a href="#">io.h</a> . . . . .	2555
contrib/libio-io/l4/io/ <a href="#">types.h</a> . . . . .	3268
l4/cxx/ <a href="#">alloc.h</a>	
Alloc list . . . . .	2558
l4/cxx/ <a href="#">arith</a> . . . . .	2559
l4/cxx/ <a href="#">atomic.h</a>	
Atomic template . . . . .	3304
l4/cxx/ <a href="#">avl_map</a>	
AVL map . . . . .	2560
l4/cxx/ <a href="#">avl_set</a>	
AVL set . . . . .	2563
l4/cxx/ <a href="#">avl_tree</a>	
AVL tree . . . . .	2568
l4/cxx/ <a href="#">basic_ostream</a>	
Basic IO stream . . . . .	2574
l4/cxx/ <a href="#">basic_vector.h</a>	
Basic vector . . . . .	2578
l4/cxx/ <a href="#">bitfield</a> . . . . .	2579
l4/cxx/ <a href="#">bitmap</a> . . . . .	2581
l4/cxx/ <a href="#">dlist</a> . . . . .	2602
l4/cxx/ <a href="#">elide_dtor</a> . . . . .	2607
l4/cxx/ <a href="#">exceptions</a>	
Base exceptions . . . . .	2608
l4/cxx/ <a href="#">hlist</a> . . . . .	2612
l4/cxx/ <a href="#">iostream</a>	
IO Stream . . . . .	2614
l4/cxx/ <a href="#">ipc_helper</a>	
IPC helper . . . . .	2615
l4/cxx/ <a href="#">ipc_server</a>	
IPC server loop . . . . .	3096
l4/cxx/ <a href="#">ipc_stream</a>	
IPC stream . . . . .	2616
l4/cxx/ <a href="#">ipc_timeout_queue</a> . . . . .	2634
l4/cxx/ <a href="#">l4iostream</a>	
L4 IO stream . . . . .	2636
l4/cxx/ <a href="#">l4types.h</a>	
L4 Types . . . . .	2637
l4/cxx/ <a href="#">list</a> . . . . .	2638
l4/cxx/ <a href="#">list_alloc</a> . . . . .	2642
l4/cxx/ <a href="#">lock_guard.h</a>	
Lock guard implementation . . . . .	2648
l4/cxx/ <a href="#">main_thread</a>	
Main thread . . . . .	2649
l4/cxx/ <a href="#">minmax</a> . . . . .	2651



l4/cxx/numeric	2652
l4/cxx/observer	2652
l4/cxx/pair	
Pair implementation	2653
l4/cxx/ref_ptr	2655
l4/cxx/ref_ptr_list	
Implementation of a list of ref-ptr-managed objects	2658
l4/cxx/slab_alloc	2660
l4/cxx/slist	2663
l4/cxx/static_container	2666
l4/cxx/static_vector	2666
l4/cxx/std_alloc	2667
l4/cxx/std_ops	2668
l4/cxx/string	2668
l4/cxx/string.h	
String	2671
l4/cxx/thread	
Thread implementation	3258
l4/cxx/type_list	2673
l4/cxx/type_traits	2673
l4/cxx/unique_ptr	2678
l4/cxx/unique_ptr_list	
Implementation of a list of unique-ptr-managed objects	2679
l4/cxx/utlis	2681
l4/cxx/weak_ref	2681
l4/cxx/bits/bst.h	
AVL tree	2584
l4/cxx/bits/bst_base.h	
AVL tree	2588
l4/cxx/bits/bst_iter.h	
AVL tree	2591
l4/cxx/bits/list_basics.h	2594
l4/cxx/bits/smart_ptr_list.h	
Implementation of a list of smart-pointer-managed objects	2596
l4/cxx/bits/type_traits.h	2599
l4/irq/irq.h	
IRQ handling routines	2686
l4/l4re_vfs/backend	2694
l4/l4re_vfs/vfs.h	2722
l4/l4re_vfs/impl/default_ops_impl.h	2697
l4/l4re_vfs/impl/fd_store.h	2698
l4/l4re_vfs/impl/fd_store_impl.h	2699
l4/l4re_vfs/impl/ns_fs.h	2699
l4/l4re_vfs/impl/ns_fs_impl.h	2700
l4/l4re_vfs/impl/ro_file.h	2705
l4/l4re_vfs/impl/ro_file_impl.h	2705
l4/l4re_vfs/impl/vcon_stream.h	2707
l4/l4re_vfs/impl/vcon_stream_impl.h	2707
l4/l4re_vfs/impl/vfs_impl.h	2710
l4/l4virtio/l4virtio	2736
l4/l4virtio/virtio.h	2799
l4/l4virtio/virtio_block.h	2802
l4/l4virtio/virtio_input.h	2803
l4/l4virtio/virtio_net.h	2445
l4/l4virtio/virtqueue	2803
l4/l4virtio/client/l4virtio	2734
l4/l4virtio/client/virtio-block	2753
l4/l4virtio/client/virtio-net	2731

<a href="#">l4/l4virtio/server/l4virtio</a>	2738
<a href="#">l4/l4virtio/server/virtio</a>	2749
<a href="#">l4/l4virtio/server/virtio-block</a>	2757
<a href="#">l4/l4virtio/server/virtio-console</a>	2763
<a href="#">l4/l4virtio/server/virtio-console-device</a>	2769
<a href="#">l4/l4virtio/server/virtio-gpio-device</a>	2773
<a href="#">l4/l4virtio/server/virtio-i2c-device</a>	2778
<a href="#">l4/l4virtio/server/virtio-rng-device</a>	2783
<a href="#">l4/l4virtio/server/virtio-scmi-device</a>	2785
<a href="#">l4/l4virtio/server/virtio-spi-device</a>	2794
<a href="#">l4/libedid/edid.h</a>	2808
<a href="#">l4/re/cap_alloc</a>	
Abstract capability-allocator interface	2911
<a href="#">l4/re/console</a>	2846
<a href="#">l4/re/consts</a>	
Constants	3068
<a href="#">l4/re/consts.h</a>	
Constants	3056
<a href="#">l4/re/dataspace</a>	
Dataspace interface	2846
<a href="#">l4/re/dataspace-sys.h</a>	
Dataspace protocol definition	2849
<a href="#">l4/re/dbg_events</a>	2850
<a href="#">l4/re/debug</a>	
Debug interface	2927
<a href="#">l4/re/dma_space</a>	2850
<a href="#">l4/re/elf_aux.h</a>	
Auxiliary information for binaries	2853
<a href="#">l4/re/env</a>	
Environment interface	2855
<a href="#">l4/re/env.h</a>	
Environment interface	2857
<a href="#">l4/re/error_helper</a>	
Error helper	2861
<a href="#">l4/re/event</a>	2932
<a href="#">l4/re/event-sys.h</a>	2864
<a href="#">l4/re/event.h</a>	
Events	2817
<a href="#">l4/re/event_enums.h</a>	2864
<a href="#">l4/re/inhibitor</a>	2879
<a href="#">l4/re/inhibitor-sys.h</a>	2879
<a href="#">l4/re/itas</a>	2880
<a href="#">l4/re/l4aux.h</a>	
Auxiliary definitions	2881
<a href="#">l4/re/log</a>	
Log interface	2882
<a href="#">l4/re/log-sys.h</a>	
Log protocol definition	2884
<a href="#">l4/re/mem_alloc</a>	
Memory allocator interface	2884
<a href="#">l4/re/mem_alloc-sys.h</a>	
Memory allocator protocol definitions	2887
<a href="#">l4/re/mmio_space</a>	
Interface definition to emit MMIO-like accesses via IPC	2888
<a href="#">l4/re/namespace</a>	
Namespace interface	2889
<a href="#">l4/re/namespace-sys.h</a>	
Namespace protocol definitions	2892

l4/re/parent	
Parent interface	2893
l4/re/parent-sys.h	
Parent protocol definition	2895
l4/re/protocols.h	
L4Re Protocol Constants (C version)	2895
l4/re/random	
Random number generator interface definition	2896
l4/re/remote_access	2898
l4/re/rm	
Region mapper interface	2899
l4/re/rm-sys.h	
Region mapper protocol definitions	2904
l4/re/shared_cap	
Shared_cap / Shared_del_cap	2964
l4/re/unique_cap	
Unique_cap / Unique_del_cap	2969
l4/re/c/dataspace.h	
Data space C interface	2809
l4/re/c/debug.h	
Debug C interface	2405
l4/re/c/dma_space.h	
DMA space C interface	2812
l4/re/c/event.h	
Event C interface	2815
l4/re/c/event_buffer.h	2819
l4/re/c/inhibitor.h	
Inhibitor C interface	2819
l4/re/c/log.h	
Log C interface	2823
l4/re/c/mem_alloc.h	
Memory allocator C interface	2824
l4/re/c/namespace.h	
Namespace functions, C interface	2826
l4/re/c/parent.h	
Parent C interface	2827
l4/re/c/rm.h	
Region map interface, C interface	2829
l4/re/c/util/cap_alloc.h	
Capability allocator C interface	2833
l4/re/c/util/kumem_alloc.h	
Kumem allocator utility C interface	2835
l4/re/c/util/video/goos_fb.h	
Framebuffer utility functionality	2837
l4/re/c/video/colors.h	2838
l4/re/c/video/goos.h	2840
l4/re/c/video/view.h	2843
l4/re/impl/dataspace_impl.h	
Dataspace client stub implementation	2870
l4/re/impl/mem_alloc_impl.h	
Memory allocator client stub implementation	2873
l4/re/impl/namespace_impl.h	
Namespace client stub implementation	2874
l4/re/impl/rm_impl.h	
Region map client stub implementation	2877
l4/re/util/bitmap_cap_alloc	
Bitmap capability allocator	2905
l4/re/util/br_manager	2907

l4/re/util/cap	
Capability utility functions	2909
l4/re/util/cap_alloc	
Capability allocator	2914
l4/re/util/cap_alloc_impl.h	
Capability allocator implementation	2917
l4/re/util/counting_cap_alloc	
Reference-counting capability allocator	2919
l4/re/util/dataspace_svr	2924
l4/re/util/debug	2929
l4/re/util/env_ns	2931
l4/re/util/event	2934
l4/re/util/event_buffer	2937
l4/re/util/event_svr	2938
l4/re/util/icu_svr	2939
l4/re/util/item_alloc	
Item allocator	2941
l4/re/util/kumem_alloc	
Kumem allocator helper	2944
l4/re/util/meta	3213
l4/re/util/name_space_svr	2945
l4/re/util/object_registry	2951
l4/re/util/poll_timeout_kipclock	2953
l4/re/util/region_mapping	
Region handling	2954
l4/re/util/region_mapping_svr	2961
l4/re/util/shared_cap	
Shared_cap / Shared_del_cap	2966
l4/re/util/unique_cap	
Unique_cap / Unique_del_cap	2971
l4/re/util/vcon_svr	2973
l4/re/util/video/goos_fb	2974
l4/re/util/video/goos_svr	2976
l4/re/video/colors	2977
l4/re/video/goos	2979
l4/re/video/goos-sys.h	
Goos protocol definition	2982
l4/re/video/view	2983
l4/shmc/ringbuf.h	2983
l4/shmc/shmc.h	
Shared memory library header file	2992
l4/sigma0/sigma0.h	
Sigma0 interface	2997
l4/sys/_kernel_object_impl.h	3001
l4/sys/_ktrace-impl.h	
L4 kernel event tracing	3001
l4/sys/_l4_fpage.h	3003
l4/sys/_platform_control-arm.h	3007
l4/sys/_task-arm.h	3008
l4/sys/_timeout.h	3008
l4/sys/_typeinfo.h	
Type information handling	3011
l4/sys/_vcpu-arm.h	3023
l4/sys/_vm-svm.h	3024
l4/sys/_vm-vmx.h	3026
l4/sys/arm_smccc	
ARM secure monitor call functions	3032

<a href="#">l4/sys/arm_smccc.h</a>	
ARM secure monitor call functions . . . . .	3033
<a href="#">l4/sys/assert.h</a>	
Low-level assert implementation . . . . .	3298
<a href="#">l4/sys/cache.h</a>	
Cache-consistency functions . . . . .	3043
<a href="#">l4/sys/capability</a>	
<a href="#">L4::Cap</a> related definitions . . . . .	3046
<a href="#">l4/sys/compiler.h</a>	
<a href="#">L4</a> compiler related defines . . . . .	3049
<a href="#">l4/sys/consts.h</a>	
Common constants . . . . .	3058
<a href="#">l4/sys/debugger</a>	
The debugger interface specifies common debugging related definitions . . . . .	3132
<a href="#">l4/sys/debugger.h</a>	
Debugger related definitions . . . . .	3133
<a href="#">l4/sys/err.h</a>	
Error codes . . . . .	3139
<a href="#">l4/sys/exception</a>	
Exception C++ interface . . . . .	3141
<a href="#">l4/sys/factory</a>	
Common factory related definitions . . . . .	3143
<a href="#">l4/sys/factory.h</a>	
Common factory related definitions . . . . .	3146
<a href="#">l4/sys/icu</a>	
Interrupt controller . . . . .	3153
<a href="#">l4/sys/icu.h</a>	
Interrupt controller . . . . .	3154
<a href="#">l4/sys/iommu</a>	
. . . . .	3160
<a href="#">l4/sys/ipc.h</a>	
Common IPC interface . . . . .	3162
<a href="#">l4/sys/ipc_gate</a>	
The C++ IPC gate interface . . . . .	3170
<a href="#">l4/sys/ipc_gate.h</a>	
The C IPC gate interface, see <a href="#">L4::lpc_gate</a> for the C++ interface . . . . .	3172
<a href="#">l4/sys/irq</a>	
C++ Irq interface . . . . .	3175
<a href="#">l4/sys/irq.h</a>	
C Irq interface . . . . .	2688
<a href="#">l4/sys/kdebug.h</a>	
Functionality for invoking the kernel debugger . . . . .	3179
<a href="#">l4/sys/kdump.h</a>	
Functionality for dumping kernel information . . . . .	3196
<a href="#">l4/sys/kernel_object.h</a>	
Kernel object system calls . . . . .	3198
<a href="#">l4/sys/kip</a>	
. . . . .	3200
<a href="#">l4/sys/kip.h</a>	
Kernel Info Page access functions . . . . .	3343
<a href="#">l4/sys/kobject</a>	
. . . . .	3203
<a href="#">l4/sys/ktrace.h</a>	
<a href="#">L4</a> kernel event tracing . . . . .	3203
<a href="#">l4/sys/l4int.h</a>	
Fixed sized integer types, generic version . . . . .	3208
<a href="#">l4/sys/memdesc.h</a>	
Memory description functions . . . . .	3210
<a href="#">l4/sys/meta</a>	
Meta interface for getting dynamic type information about objects behind capabilities . . . . .	3214

<a href="#">l4/sys/obj_info.h</a>	
Debugger related functions	3215
<a href="#">l4/sys/pager</a>	
Pager and lo_pager C++ interface	3219
<a href="#">l4/sys/platform_control</a>	
Platform control object	3221
<a href="#">l4/sys/platform_control.h</a>	
Platform control object	3224
<a href="#">l4/sys/rcv_endpoint</a>	
The C++ Receive endpoint interface	3228
<a href="#">l4/sys/rcv_endpoint.h</a>	
Receive endpoint C interface	3229
<a href="#">l4/sys/scheduler</a>	
Scheduler object functions	3232
<a href="#">l4/sys/scheduler.h</a>	
Scheduler object functions	3234
<a href="#">l4/sys/semaphore</a>	
Semaphore class definition	3239
<a href="#">l4/sys/semaphore.h</a>	
C semaphore interface	3241
<a href="#">l4/sys/smart_capability</a>	
L4::Capability class	3244
<a href="#">l4/sys/snd_destination</a>	
The C++ Sender destination interface	3247
<a href="#">l4/sys/snd_destination.h</a>	
Sender destination endpoint C interface	3249
<a href="#">l4/sys/task</a>	
Common task related definitions	3250
<a href="#">l4/sys/task.h</a>	
Common task related definitions	3253
<a href="#">l4/sys/thread</a>	
Common thread related definitions	3260
<a href="#">l4/sys/thread.h</a>	
Common thread related definitions	2526
<a href="#">l4/sys/thread_group</a>	3262
<a href="#">l4/sys/thread_group.h</a>	3264
<a href="#">l4/sys/typeinfo_svr</a>	
Type information server template	3266
<a href="#">l4/sys/types.h</a>	
Common L4 ABI Data Types	3268
<a href="#">l4/sys/utcb.h</a>	
UTCB definitions	3281
<a href="#">l4/sys/vcon</a>	
C++ Virtual console interface	3287
<a href="#">l4/sys/vcon.h</a>	
Virtual console interface	3289
<a href="#">l4/sys/vcpu.h</a>	
VCPU API	3393
<a href="#">l4/sys/vcpu_context</a>	
Hardware vCPU context interface	3295
<a href="#">l4/sys/vcpu_context.h</a>	3296
<a href="#">l4/sys/vm</a>	
Virtualization interface	3296
<a href="#">l4/sys/cxx/capability.h</a>	3065
<a href="#">l4/sys/cxx/consts</a>	3069
<a href="#">l4/sys/cxx/ipc_array</a>	3070
<a href="#">l4/sys/cxx/ipc_basics</a>	3073
<a href="#">l4/sys/cxx/ipc_client</a>	3077

<a href="#">l4/sys/cxx/ipc_epiface</a>	3079
<a href="#">l4/sys/cxx/ipc_iface</a>	
Interface Definition Language	3083
<a href="#">l4/sys/cxx/ipc_legacy</a>	3095
<a href="#">l4/sys/cxx/ipc_ret_array</a>	3095
<a href="#">l4/sys/cxx/ipc_server</a>	3098
<a href="#">l4/sys/cxx/ipc_server_loop</a>	3103
<a href="#">l4/sys/cxx/ipc_string</a>	3106
<a href="#">l4/sys/cxx/ipc_types</a>	3107
<a href="#">l4/sys/cxx/ipc_varg</a>	3116
<a href="#">l4/sys/cxx/limits</a>	3121
<a href="#">l4/sys/cxx/smart_capability_1x</a>	3123
<a href="#">l4/sys/cxx/types</a>	3126
<a href="#">l4/util/assert.h</a>	
Some useful assert-style macros	3301
<a href="#">l4/util/atomic.h</a>	
Atomic operations header and generic implementations	3306
<a href="#">l4/util/backtrace.h</a>	
Backtrace	3313
<a href="#">l4/util/base64.h</a>	
Base 64 encoding and decoding functions adapted from Bob Trower 08/04/01	3315
<a href="#">l4/util/bitops.h</a>	
Bit manipulation functions	3317
<a href="#">l4/util/elf.h</a>	
ELF definition	3322
<a href="#">l4/util/getopt.h</a>	
Getopt	3339
<a href="#">l4/util/keymap.h</a>	
Event to ASCII key mapping	3341
<a href="#">l4/util/kip.h</a>	3348
<a href="#">l4/util/kprintf.h</a>	
Printf using the kernel debugger	3349
<a href="#">l4/util/l4_macros.h</a>	
Some useful generic macros, L4f version	2522
<a href="#">l4/util/l4mod.h</a>	
L4mod structures and constants	3350
<a href="#">l4/util/list_alloc.h</a>	
Simple list-based allocator	3352
<a href="#">l4/util/lock.h</a>	
Simple lock implementation	3355
<a href="#">l4/util/mb_info.h</a>	
Multiboot info structure as defined by GRUB	3357
<a href="#">l4/util/parse_cmd.h</a>	
Comfortable command-line parsing	3365
<a href="#">l4/util/printf_helpers.h</a>	3367
<a href="#">l4/util/rand.h</a>	
Simple Pseudo-Random Number Generator	3367
<a href="#">l4/util/splitlog2.h</a>	
Split a range in log2 aligned and size-aligned chunks	3368
<a href="#">l4/util/thread.h</a>	
Low-level Thread Functions	2536
<a href="#">l4/util/util.h</a>	3370
<a href="#">l4/vbus/vbus</a>	3371
<a href="#">l4/vbus/vbus.h</a>	
Description of the vbus C API	3373
<a href="#">l4/vbus/vbus_generic</a>	3376
<a href="#">l4/vbus/vbus_gpio</a>	3377
<a href="#">l4/vbus/vbus_gpio-ops.h</a>	3378

<a href="#">l4/vbus/vbus_gpio.h</a>	3378
<a href="#">l4/vbus/vbus_i2c.h</a>	3379
<a href="#">l4/vbus/vbus_inhibitor.h</a>	3380
<a href="#">l4/vbus/vbus_interfaces.h</a>	
This header contains the definition of VBUS sub-interfaces and convenience functions to work with the interface IDs	3380
<a href="#">l4/vbus/vbus_mcspi.h</a>	3383
<a href="#">l4/vbus/vbus_pci</a>	3384
<a href="#">l4/vbus/vbus_pci-ops.h</a>	3385
<a href="#">l4/vbus/vbus_pci.h</a>	3385
<a href="#">l4/vbus/vbus_pm-ops.h</a>	3386
<a href="#">l4/vbus/vbus_pm.h</a>	3386
<a href="#">l4/vbus/vbus_types.h</a>	
This header file contains descriptions of vbus related data types and constants	3386
<a href="#">l4/vbus/vdevice-ops.h</a>	3390
<a href="#">l4/vcpu/vcpu</a>	
VCPU support library (C++ interface)	3391
<a href="#">l4/vcpu/vcpu.h</a>	
VCPU support library (C interface)	3396
<a href="#">x86/l4/sys/__kip-arch.h</a>	2488
<a href="#">x86/l4/sys/__vcpu-arch.h</a>	
X86-specific vCPU interface	2497
<a href="#">x86/l4/sys/ktrace_events.h</a>	2509
<a href="#">x86/l4/sys/linkage.h</a>	
Linkage	2514
<a href="#">x86/l4/sys/segment.h</a>	
Segment handling (x86)	2454
<a href="#">x86/l4/sys/vm.h</a>	2520
<a href="#">x86/l4/sys/arch/cache.h</a>	
Cache functions	3044
<a href="#">x86/l4/sys/arch/consts.h</a>	
Common L4 constants, x86 version	3064
<a href="#">x86/l4/sys/arch/ipc.h</a>	
L4 IPC System Calls, x86	3168
<a href="#">x86/l4/sys/arch/kip.h</a>	3349
<a href="#">x86/l4/sys/arch/l4int.h</a>	
Fixed sized integer types, x86 version	3209
<a href="#">x86/l4/sys/arch/platform_control.h</a>	3227
<a href="#">x86/l4/sys/arch/task.h</a>	3257
<a href="#">x86/l4/sys/arch/thread.h</a>	2538
<a href="#">x86/l4/sys/arch/utcb.h</a>	
UTCB definitions for x86	3285
<a href="#">x86/l4/util/bitops_arch.h</a>	
X86 bit manipulation functions	2543
<a href="#">x86/l4/util/cpu.h</a>	
CPU related functions	2549
<a href="#">x86/l4/util/irq.h</a>	
Some PIC and hardware interrupt related functions	2692
<a href="#">x86/l4/util/mbi_argv.h</a>	
Command line handling	2553
<a href="#">x86/l4/util/perform.h</a>	
Performance Monitoring using P5/P6 Measurement Counters	2462
<a href="#">x86/l4/util/port_io.h</a>	
X86 port I/O	2472
<a href="#">x86/l4/util/rdtsc.h</a>	
Timestamp counter related functions	2480
<a href="#">x86/l4/util/spin.h</a>	
Spinning for x86	2486



---

x86/l4/util/arch/ <a href="#">l4_macros.h</a>	
Main function . . . . .	<a href="#">2523</a>
x86/l4/util/arch/ <a href="#">thread.h</a> . . . . .	<a href="#">2538</a>




## Chapter 13

# Topic Documentation

### 13.1 Base API

Interfaces for all kinds of base functionality.

Collaboration diagram for Base API:



## Topics

- Basic Macros . . . . . 152  
*L4 standard macros for header files, function definitions, and public APIs etc.*
- Fiasco extensions . . . . . 157

<i>Extensions of the Fiasco L4 implementation.</i>	
• Flexpages . . . . .	173
<i>Flexpage-related API.</i>	
• C++ IPC Interface Definition . . . . .	191
<i>APIs for defining IPC interfaces using C++ as language.</i>	
• Cache Consistency . . . . .	192
<i>Various functions for cache consistency.</i>	
• Memory related . . . . .	196
<i>Memory related constants, data types and functions.</i>	
• Error codes . . . . .	205
<i>Common error codes.</i>	
• Object Invocation . . . . .	207
<i>API for L4 object invocation.</i>	
• Kernel Objects . . . . .	273
<i>API of kernel objects.</i>	
• Kernel Interface Page . . . . .	425
<i>Kernel Interface Page.</i>	
• Capabilities . . . . .	437
<i>C interface for capabilities.</i>	
• Memory Operations . . . . .	441
<i>Operations for memory access.</i>	
• Integer Types . . . . .	444

## Files

- file [cache.h](#)  
*Cache-consistency functions.*
- file [compiler.h](#)  
*L4 compiler related defines.*
- file [consts.h](#)  
*Common constants.*
- file [debugger.h](#)  
*Debugger related definitions.*
- file [factory.h](#)  
*Common factory related definitions.*
- file [icu](#)  
*Interrupt controller.*
- file [icu.h](#)  
*Interrupt controller.*

- file [ipc.h](#)  
*Common IPC interface.*
- file [irq.h](#)  
*C Irq interface.*
- file [kip](#)
- file [kip.h](#)  
*Kernel Info Page access functions.*
- file [memdesc.h](#)  
*Memory description functions.*
- file [semaphore.h](#)  
*C semaphore interface.*
- file [types.h](#)  
*Common L4 ABI Data Types.*
- file [consts.h](#)  
*Common L4 constants, arm version.*
- file [consts.h](#)  
*Common L4 constants, arm version.*
- file [consts.h](#)  
*Common L4 constants, AMD64 version.*
- file [consts.h](#)  
*Common L4 constants, x86 version.*
- file [ipc.h](#)  
*L4 IPC System Calls, x86.*

### 13.1.1 Detailed Description

Interfaces for all kinds of base functionality.

Some notes on Inter Process Communication (IPC)

IPC in L4 is always synchronous and unbuffered: a message is transferred from the sender to the recipient if and only if the recipient has invoked a corresponding IPC operation. The sender blocks until this happens or a timeout specified by the sender elapsed without the destination becoming ready to receive.

### 13.1.2 Basic Macros

L4 standard macros for header files, function definitions, and public APIs etc.

Collaboration diagram for Basic Macros:



## Files

- file [linkage.h](#)  
*Linkage.*
- file [linkage.h](#)  
*Linkage.*
- file [linkage.h](#)  
*Linkage.*

## Macros

- **#define L4\_INLINE**  
*L4 Inline function attribute.*
- **#define L4\_ALWAYS\_INLINE**  
*Always inline a function.*
- **#define L4\_BEGIN\_DECLS**  
*Start section with C types and functions.*
- **#define L4\_END\_DECLS**  
*End section with C types and functions.*
- **#define L4\_NOTHROW**  
*Mark a function declaration and definition as never throwing an exception.*
- **#define L4\_EXPORT**  
*Attribute to mark functions, variables, and data types as being exported from a library.*
- **#define L4\_HIDDEN**  
*Attribute to mark functions, variables, and data types as being explicitly hidden from users of a library.*
- **#define L4\_CONSTEXPR**  
*Constexpr function attribute.*
- **#define L4\_NORETURN**  
*Noreturn function attribute.*
- **#define L4\_NOINSTRUMENT**  
*No instrumentation function attribute.*
- **#define L4\_LIKELY(x)**  
*Expression is likely to execute.*
- **#define L4\_UNLIKELY(x)**  
*Expression is unlikely to execute.*
- **#define L4\_STICKY(x)**  
*Mark symbol sticky (even not there).*
- **#define L4\_DEPRECATED(s)**  
*Mark symbol deprecated.*
- **#define L4\_stringify\_helper(x)**  
*stringify helper.*
- **#define L4\_stringify(x)**  
*stringify.*
- **#define L4\_CV**  
*Define calling convention.*
- **#define L4\_CV**  
*Define calling convention.*
- **#define L4\_CV**  
*Define calling convention.*
- **#define L4\_CV**  
*Define calling convention.*

## Functions

- unsigned long [l4\\_align\\_stack\\_for\\_direct\\_fncall](#) (unsigned long stack)  
*Specify the desired alignment of the stack pointer.*
- void [l4\\_barrier](#) (void)  
*Memory barrier.*
- void [l4\\_mb](#) (void)  
*Memory barrier.*
- void [l4\\_wmb](#) (void)  
*Write memory barrier.*
- [L4\\_NORETURN](#) void [l4\\_infinite\\_loop](#) (void)  
*Infinite loop.*

### 13.1.2.1 Detailed Description

[L4](#) standard macros for header files, function definitions, and public APIs etc.

#### Include File

```
#include <l4/sys/compiler.h>
```

### 13.1.2.2 Macro Definition Documentation

#### 13.1.2.2.1 L4\_EXPORT

```
#define L4_EXPORT
```

Attribute to mark functions, variables, and data types as being exported from a library.

All data types, functions, and global variables that shall be exported from a library shall be marked with this attribute. The default may become to hide everything that is not marked as `L4_EXPORT` from the users of a library and provide the possibility for aggressive optimization of all those internal functionality of a library.

#### Usage:

```
class L4_EXPORT My_class
{
    ...
};

int L4_EXPORT function(void);

int L4_EXPORT global_data; // global data is not recommended
```

Definition at line 214 of file [compiler.h](#).

Referenced by [l4io\\_iterate\\_devices\(\)](#), [l4io\\_lookup\\_device\(\)](#), [l4io\\_lookup\\_resource\(\)](#), [l4io\\_release\\_iomem\(\)](#), [l4io\\_release\\_ioport\(\)](#), [l4io\\_request\\_all\\_ioports\(\)](#), [l4io\\_request\\_icu\(\)](#), [l4io\\_request\\_iomem\(\)](#), [l4io\\_request\\_iomem\\_region\(\)](#), [l4io\\_request\\_ioport\(\)](#), [l4io\\_request\\_resource\\_iomem\(\)](#), [l4re\\_inhibitor\\_acquire\(\)](#), and [l4re\\_inhibitor\\_release\(\)](#).



### 13.1.2.2.2 L4\_HIDDEN

```
#define L4_HIDDEN
```

Attribute to mark functions, variables, and data types as being explicitly hidden from users of a library.

This attribute is intended for functions, data, and data types that shall never be visible outside of a library. In particular, for shared libraries this may result in much faster code within the library and short linking times.

```
class L4_HIDDEN My_class
{
    ...
};

int L4_HIDDEN function(void);

int L4_HIDDEN global_data; // global data is not recommended
```

Definition at line 211 of file [compiler.h](#).

### 13.1.2.2.3 L4\_NOTHROW

```
#define L4_NOTHROW
```

Mark a function declaration and definition as never throwing an exception.

(Also for C code).

This macro shall be used to mark C and C++ functions that never throw any exception. Note that also C functions may throw exceptions according to the compilers ABI and shall be marked with L4\_NOTHROW if they never do. In C++ this is equivalent to `throw()`.

```
int foo() L4_NOTHROW;
...
int foo() L4_NOTHROW
{
    ...
    return result;
}
```

Definition at line 161 of file [compiler.h](#).

Referenced by [\\_\\_l4\\_kdebug\\_3\\_text\(\)](#), [\\_\\_l4\\_kdebug\\_op\(\)](#), [\\_\\_l4\\_kdebug\\_op\\_1\(\)](#), [\\_\\_l4\\_kdebug\\_text\(\)](#), [l4\\_msgtag\\_t::flags\(\)](#), [l4\\_msgtag\\_t::has\\_error\(\)](#), [l4\\_msgtag\\_t::is\\_exception\(\)](#), [l4\\_msgtag\\_t::is\\_io\\_page\\_fault\(\)](#), [l4\\_msgtag\\_t::is\\_page\\_fault\(\)](#), [l4\\_msgtag\\_t::is\\_sigma0\(\)](#), [l4\\_msgtag\\_t::items\(\)](#), [l4\\_arm\\_smccc\\_call\(\)](#), [l4\\_bytes\\_to\\_mwords\(\)](#), [l4\\_cache\\_clean\\_data\(\)](#), [l4\\_cache\\_coherent\(\)](#), [l4\\_cache\\_dma\\_coherent\(\)](#), [l4\\_cache\\_dma\\_coherent\\_full\(\)](#), [l4\\_cache\\_flush\\_data\(\)](#), [l4\\_cache\\_inv\\_data\(\)](#), [l4\\_capability\\_equal\(\)](#), [l4\\_capability\\_next\(\)](#), [l4\\_debugger\\_add\\_image\\_info\(\)](#), [l4\\_debugger\\_get\\_object\\_name\(\)](#), [l4\\_debugger\\_global\\_id\(\)](#), [l4\\_debugger\\_kobj\\_to\\_id\(\)](#), [l4\\_debugger\\_query\\_log\\_name\(\)](#), [l4\\_debugger\\_query\\_log\\_typeid\(\)](#), [l4\\_debugger\\_query\\_obj\\_infos\(\)](#), [l4\\_debugger\\_query\\_object\\_name\(\)](#), [l4\\_debugger\\_set\\_object\\_name\(\)](#), [l4\\_debugger\\_switch\\_log\(\)](#), [l4\\_error\(\)](#), [l4\\_factory\\_create\(\)](#), [l4\\_factory\\_create\\_factory\(\)](#), [l4\\_factory\\_create\\_gate\(\)](#), [l4\\_factory\\_create\\_irq\(\)](#), [l4\\_factory\\_create\\_task\(\)](#), [l4\\_factory\\_create\\_thread\(\)](#), [l4\\_factory\\_create\\_thread\\_group\(\)](#), [l4\\_factory\\_create\\_vcpu\\_context\(\)](#), [l4\\_factory\\_create\\_vm\(\)](#), [l4\\_fpage\(\)](#), [l4\\_fpage\\_all\(\)](#), [l4\\_fpage\\_contains\(\)](#), [l4\\_fpage\\_invalid\(\)](#), [l4\\_fpage\\_ioport\(\)](#), [l4\\_fpage\\_memaddr\(\)](#), [l4\\_fpage\\_obj\(\)](#), [l4\\_fpage\\_page\(\)](#), [l4\\_fpage\\_rights\(\)](#), [l4\\_fpage\\_set\\_rights\(\)](#), [l4\\_fpage\\_size\(\)](#), [l4\\_fpage\\_type\(\)](#), [l4\\_icu\\_bind\(\)](#), [l4\\_icu\\_bind\\_u\(\)](#), [l4\\_icu\\_info\(\)](#), [l4\\_icu\\_info\\_u\(\)](#), [l4\\_icu\\_mask\(\)](#), [l4\\_icu\\_mask\\_u\(\)](#), [l4\\_icu\\_msi\\_info\(\)](#), [l4\\_icu\\_msi\\_info\\_u\(\)](#), [l4\\_icu\\_set\\_mode\(\)](#), [l4\\_icu\\_set\\_mode\\_u\(\)](#), [l4\\_icu\\_unbind\(\)](#), [l4\\_icu\\_unbind\\_u\(\)](#), [l4\\_icu\\_unmask\(\)](#), [l4\\_icu\\_unmask\\_u\(\)](#), [l4\\_iofpage\(\)](#), [l4\\_ipc\(\)](#), [l4\\_ipc\\_call\(\)](#), [l4\\_ipc\\_error\(\)](#), [l4\\_ipc\\_error\\_code\(\)](#), [l4\\_ipc\\_is\\_rcv\\_error\(\)](#), [l4\\_ipc\\_is\\_snd\\_error\(\)](#), [l4\\_ipc\\_receive\(\)](#), [l4\\_ipc\\_reply\\_and\\_wait\(\)](#), [l4\\_ipc\\_send\(\)](#), [l4\\_ipc\\_send\\_and\\_wait\(\)](#), [l4\\_ipc\\_sleep\(\)](#), [l4\\_ipc\\_sleep\\_ms\(\)](#), [l4\\_ipc\\_sleep\\_us\(\)](#), [l4\\_ipc\\_timeout\(\)](#), [l4\\_ipc\\_to\\_errno\(\)](#), [l4\\_ipc\\_wait\(\)](#), [l4\\_irq\\_bind\\_vcpu\(\)](#), [l4\\_irq\\_bind\\_vcpu\\_u\(\)](#), [l4\\_irq\\_detach\(\)](#), [l4\\_irq\\_detach\\_u\(\)](#), [l4\\_irq\\_receive\(\)](#), [l4\\_irq\\_receive\\_u\(\)](#), [l4\\_irq\\_trigger\(\)](#), [l4\\_irq\\_trigger\\_u\(\)](#), [l4\\_irq\\_unmask\(\)](#), [l4\\_irq\\_unmask\\_u\(\)](#), [l4\\_irq\\_wait\(\)](#), [l4\\_irq\\_wait\\_u\(\)](#), [l4\\_is\\_fpage\\_valid\(\)](#), [l4\\_is\\_fpage\\_writable\(\)](#), [l4\\_is\\_invalid\\_cap\(\)](#), [l4\\_is\\_valid\\_cap\(\)](#), [l4\\_kd\\_enter\(\)](#), [l4\\_kernel\\_info\\_get\\_mem\\_desc\\_end\(\)](#), [l4\\_kernel\\_info\\_get\\_mem\\_desc\\_is\\_virtual\(\)](#), [l4\\_kernel\\_info\\_get\\_mem\\_desc\\_start\(\)](#), [l4\\_kernel\\_info\\_get\\_mem\\_desc\\_subtype\(\)](#), [l4\\_kernel\\_info\\_get\\_mem\\_desc\\_type\(\)](#), [l4\\_kernel\\_info\\_get\\_mem\\_descs\(\)](#), [l4\\_kernel\\_info\\_get\\_num\\_mem\\_descs\(\)](#),

l4\_kernel\_info\_set\_mem\_desc(), l4\_kernel\_info\_version\_offset(), l4\_kip(), l4\_kip\_clock(), l4\_kip\_clock\_lw(), l4\_kip\_clock\_ns(), l4\_kip\_version(), l4\_kip\_version\_string(), l4\_map\_control(), l4\_map\_obj\_control(), l4\_msgtag(), l4\_msgtag\_flags(), l4\_msgtag\_has\_error(), l4\_msgtag\_is\_exception(), l4\_msgtag\_is\_io\_page\_fault(), l4\_msgtag\_is\_page\_fault(), l4\_msgtag\_is\_sigma0(), l4\_msgtag\_items(), l4\_msgtag\_label(), l4\_msgtag\_words(), l4\_obj\_fpage(), l4\_platform\_ctl\_cpu\_allow\_shutdown(), l4\_platform\_ctl\_cpu\_disable(), l4\_platform\_ctl\_cpu\_enable(), l4\_platform\_ctl\_set\_task\_asid(), l4\_platform\_ctl\_system\_shutdown(), l4\_platform\_ctl\_system\_suspend(), l4\_rcv\_timeout(), l4\_round\_page(), l4\_round\_size(), l4\_sched\_cpu\_set(), l4\_sched\_param(), l4\_scheduler\_idle\_time(), l4\_scheduler\_info(), l4\_scheduler\_info\_with\_classes(), l4\_scheduler\_is\_online(), l4\_scheduler\_run\_thread(), l4\_semaphore\_down(), l4\_semaphore\_up(), l4\_sleep(), l4\_sleep\_forever(), l4\_snd\_timeout(), l4\_sndpage\_add(), l4\_task\_add\_ku\_mem(), l4\_task\_cap\_equal(), l4\_task\_cap\_valid(), l4\_task\_delete\_obj(), l4\_task\_map(), l4\_task\_release\_cap(), l4\_task\_unmap(), l4\_task\_unmap\_batch(), l4\_task\_vgicc\_map(), l4\_thread\_arm\_set\_tpidruro(), l4\_thread\_control\_alien(), l4\_thread\_control\_bind(), l4\_thread\_control\_commit(), l4\_thread\_control\_exc\_handler(), l4\_thread\_control\_pager(), l4\_thread\_control\_start(), l4\_thread\_ex\_regs(), l4\_thread\_ex\_regs\_ret(), l4\_thread\_ex\_regs\_ret\_u(), l4\_thread\_ex\_regs\_u(), l4\_thread\_group\_add(), l4\_thread\_group\_remove(), l4\_thread\_modify\_sender\_add(), l4\_thread\_modify\_sender\_commit(), l4\_thread\_modify\_sender\_start(), l4\_thread\_register\_del\_irq(), l4\_thread\_register\_doorbell\_irq(), l4\_thread\_stats\_time(), l4\_thread\_switch(), l4\_thread\_vcpu\_control(), l4\_thread\_vcpu\_control\_ext(), l4\_thread\_vcpu\_control\_ext\_u(), l4\_thread\_vcpu\_control\_u(), l4\_thread\_vcpu\_resume\_commit(), l4\_thread\_vcpu\_resume\_start(), l4\_thread\_yield(), l4\_timeout(), l4\_timeout\_abs(), l4\_timeout\_get(), l4\_timeout\_is\_absolute(), l4\_timeout\_rel(), l4\_timeout\_rel\_get(), l4\_touch\_ro(), l4\_touch\_rw(), l4\_trunc\_page(), l4\_trunc\_size(), l4\_usleep(), l4\_utcb(), l4\_utcb\_br(), l4\_utcb\_exc(), l4\_utcb\_exc\_is\_ex\_regs\_exception(), l4\_utcb\_exc\_is\_ex\_regs\_exception(), l4\_utcb\_exc\_is\_pf(), l4\_utcb\_exc\_is\_pf(), l4\_utcb\_exc\_pc(), l4\_utcb\_exc\_pc(), l4\_utcb\_exc\_pc\_set(), l4\_utcb\_exc\_pfa(), l4\_utcb\_exc\_pfa(), l4\_utcb\_exc\_typeval(), l4\_utcb\_exc\_typeval(), l4\_utcb\_inherit\_fpu(), l4\_utcb\_mr(), l4\_utcb\_mr64\_idx(), l4\_utcb\_tcr(), l4\_vcon\_get\_attr(), l4\_vcon\_get\_attr\_u(), l4\_vcon\_read(), l4\_vcon\_read\_u(), l4\_vcon\_read\_with\_flags(), l4\_vcon\_send(), l4\_vcon\_send\_u(), l4\_vcon\_set\_attr(), l4\_vcon\_set\_attr\_raw(), l4\_vcon\_set\_attr\_u(), l4\_vcon\_write(), l4\_vcon\_write\_u(), l4\_vcpu\_check\_version(), l4\_vm\_vmx\_clear(), l4\_vm\_vmx\_field\_len(), l4\_vm\_vmx\_field\_order(), l4\_vm\_vmx\_get\_caps(), l4\_vm\_vmx\_get\_caps\_default1(), l4\_vm\_vmx\_get\_cr2\_index(), l4\_vm\_vmx\_get\_hw\_vmcs(), l4\_vm\_vmx\_ptr\_load(), l4\_vm\_vmx\_read(), l4\_vm\_vmx\_read\_16(), l4\_vm\_vmx\_read\_32(), l4\_vm\_vmx\_read\_64(), l4\_vm\_vmx\_read\_nat(), l4\_vm\_vmx\_set\_hw\_vmcs(), l4\_vm\_vmx\_write(), l4\_vm\_vmx\_write\_16(), l4\_vm\_vmx\_write\_32(), l4\_vm\_vmx\_write\_64(), l4\_vm\_vmx\_write\_nat(), l4re\_debug\_obj\_debug(), l4re\_dma\_space\_associate(), l4re\_dma\_space\_map(), l4re\_dma\_space\_unmap(), l4re\_ds\_allocate(), l4re\_ds\_clear(), l4re\_ds\_copy\_in(), l4re\_ds\_flags(), l4re\_ds\_info(), l4re\_ds\_map\_info(), l4re\_ds\_size(), l4re\_env(), l4re\_env\_cap\_entry\_t::l4re\_env\_cap\_entry\_t(), l4re\_env\_cap\_entry\_t::l4re\_env\_cap\_entry\_t(), l4re\_env\_get\_cap(), l4re\_env\_get\_cap\_e(), l4re\_env\_get\_cap\_l(), l4re\_event\_get\_axis\_info(), l4re\_event\_get\_buffer(), l4re\_event\_get\_num\_streams(), l4re\_event\_get\_stream\_info(), l4re\_event\_get\_stream\_info\_for\_id(), l4re\_kip(), l4re\_log\_print(), l4re\_log\_print\_srv(), l4re\_log\_printn(), l4re\_log\_printn\_srv(), l4re\_ma\_alloc(), l4re\_ma\_alloc\_align(), l4re\_ma\_alloc\_align\_srv(), l4re\_ns\_query\_srv(), l4re\_ns\_query\_to\_srv(), l4re\_ns\_register\_obj\_srv(), l4re\_rm\_attach(), l4re\_rm\_attach\_srv(), l4re\_rm\_detach(), l4re\_rm\_detach\_ds(), l4re\_rm\_detach\_ds\_unmap(), l4re\_rm\_detach\_srv(), l4re\_rm\_detach\_unmap(), l4re\_rm\_find(), l4re\_rm\_find\_srv(), l4re\_rm\_free\_area(), l4re\_rm\_free\_area\_srv(), l4re\_rm\_get\_info(), l4re\_rm\_get\_info\_srv(), l4re\_rm\_reserve\_area(), l4re\_rm\_reserve\_area\_srv(), l4re\_rm\_show\_lists(), l4re\_rm\_show\_lists\_srv(), l4re\_util\_cap\_alloc(), l4re\_util\_cap\_free(), l4re\_util\_cap\_free\_um(), l4re\_util\_cap\_last(), l4re\_util\_kumem\_alloc(), l4re\_video\_goos\_create\_buffer(), l4re\_video\_goos\_create\_view(), l4re\_video\_goos\_delete\_buffer(), l4re\_video\_goos\_delete\_view(), l4re\_video\_goos\_get\_static\_buffer(), l4re\_video\_goos\_get\_view(), l4re\_video\_goos\_info(), l4re\_video\_goos\_refresh(), l4re\_video\_view\_get\_info(), l4re\_video\_view\_refresh(), l4re\_video\_view\_set\_info(), l4re\_video\_view\_set\_viewport(), l4re\_video\_view\_stack(), l4util\_micros2l4to(), l4vcpu\_ext\_alloc(), l4vcpu\_irq\_disable(), l4vcpu\_irq\_disable\_save(), l4vcpu\_irq\_enable(), l4vcpu\_irq\_restore(), l4vcpu\_is\_irq\_entry(), l4vcpu\_is\_page\_fault\_entry(), l4vcpu\_print\_state(), l4vcpu\_wait\_for\_event(), l4virtio\_config\_queue(), l4virtio\_device\_config\_ds(), l4virtio\_device\_notification\_irq(), l4virtio\_register\_ds(), l4virtio\_set\_status(), l4\_msgtag\_t::label(), l4\_msgtag\_t::label(), and l4\_msgtag\_t::words().

### 13.1.2.3 Function Documentation

#### 13.1.2.3.1 l4\_align\_stack\_for\_direct\_fncall()

```
unsigned long l4_align_stack_for_direct_fncall (
    unsigned long stack) [inline]
```

Specify the desired alignment of the stack pointer.

**BIGGEST\_ALIGNMENT** provides the largest alignment ever used for any data type on the target machine. This is normally identical to desired stack alignment. Align stack pointer for directly invoked functions.

The stack needs to be aligned to `L4_STACK_ALIGN` for being able to access certain data on the stack. On x86/AMD64, a function call is performed using the 'call' instruction decrementing the stack pointer and writing the return address onto the stack. The called function considers this when adapting the stack pointer after function entry. If the called function was not invoked by a 'call' instruction, the stack pointer is actually off by a machine word leading to stack alignment issues when executing SSE instructions.

This function fixes the stack pointer for directly invoked functions. For architectures not automatically pushing the stack pointer during a function call, just enforce the `L4_STACK_ALIGN` alignment.

Definition at line 278 of file [compiler.h](#).

References [L4\\_INLINE](#).

### 13.1.2.3.2 l4\_infinite\_loop()

```
L4_NORETURN void l4_infinite_loop (
    void ) [inline]
```


Infinite loop.

Will never return. Use [l4\\_sleep\\_forever\(\)](#) if at all possible.

Definition at line 352 of file [compiler.h](#).

References [l4\\_barrier\(\)](#), [L4\\_INLINE](#), and [L4\\_NORETURN](#).


Here is the call graph for this function:



### 13.1.3 Fiasco extensions

Extensions of the Fiasco [L4](#) implementation.

Collaboration diagram for Fiasco extensions:



## Topics

- Kernel Debugger . . . . . 161  
*Kernel debugger related functionality.*
- Kernel Information Dump . . . . . 169  
*Kernel information dumping related functionality.*
- Kernel Tracing . . . . . 170  
*Kernel tracing related functionality.*

## Files

- file [\\_\\_ktrace-impl.h](#)  
*L4 kernel event tracing.*
- file [ktrace.h](#)  
*L4 kernel event tracing.*
- file [obj\\_info.h](#)  
*Debugger related functions.*
- file [segment.h](#)  
*Segment handling (AMD64).*
- file [segment.h](#)  
*Segment handling (x86).*

## Functions

- long [fiasco\\_ldt\\_set](#) ([l4\\_cap\\_idx\\_t](#) task, void \*ldt, unsigned int num\_desc, unsigned int entry\_number\_start, [l4\\_utcb\\_t](#) \*utcb)  
*Set LDT segments descriptors.*
- long [fiasco\\_gdt\\_set](#) ([l4\\_cap\\_idx\\_t](#) thread, void \*desc, unsigned int size, unsigned int entry\_number\_start, [l4\\_utcb\\_t](#) \*utcb)  
*Set GDT segment descriptors.*
- unsigned [fiasco\\_gdt\\_get\\_entry\\_offset](#) ([l4\\_cap\\_idx\\_t](#) thread, [l4\\_utcb\\_t](#) \*utcb)  
*Return the offset of the entry in the GDT.*

### 13.1.3.1 Detailed Description

Extensions of the Fiasco [L4](#) implementation.

### 13.1.3.2 Function Documentation

#### 13.1.3.2.1 fiasco\_gdt\_get\_entry\_offset()

```
unsigned fiasco_gdt_get_entry_offset (
    l4_cap_idx_t thread,
    l4_utcb_t * utcb) [inline]
```

Return the offset of the entry in the GDT.


##### Parameters

<i>thread</i>	Thread to get info from.
<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. See <a href="#">l4_utcb</a> .

Definition at line 166 of file [segment.h](#).

References [l4\\_ipc\\_call\(\)](#), [L4\\_IPC\\_NEVER](#), [l4\\_msgtag\(\)](#), [L4\\_PROTO\\_THREAD](#), and [L4\\_THREAD\\_X86\\_GDT\\_OP](#).

Here is the call graph for this function:



#### 13.1.3.2.2 fiasco\_gdt\_set()

```
long fiasco_gdt_set (
    l4_cap_idx_t thread,
    void * desc,
    unsigned int size,
    unsigned int entry_number_start,
    l4_utcb_t * utcb) [inline]
```

Set GDT segment descriptors.

Fiasco supports 4 consecutive entries, starting at the value returned by [fiasco\\_gdt\\_get\\_entry\\_offset\(\)](#).

##### Parameters

<i>thread</i>	Thread to set the GDT entry for.
<i>desc</i>	Pointer to GDT descriptors.

<i>size</i>	Size of the descriptors in bytes (multiple of 8).
<i>entry_number_start</i>	Entry number to start (valid values: 0-3).
<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. See <a href="#">l4_utcb</a> .


### Return values

<i>&lt;0</i>	At least one provided GDT descriptor is considered unsafe by the kernel, and not all selected GDT descriptors have been updated.
<i>L4_EOK</i>	Success.

Definition at line 220 of file [segment.h](#).

References [l4\\_ipc\\_call\(\)](#), [L4\\_IPC\\_NEVER](#), [l4\\_msgtag\(\)](#), [L4\\_PROTO\\_THREAD](#), and [L4\\_THREAD\\_X86\\_GDT\\_OP](#).

Here is the call graph for this function:



### 13.1.3.2.3 fiasco\_ldt\_set()

```

long fiasco_ldt_set (
    l4_cap_idx_t task,
    void * ldt,
    unsigned int num_desc,
    unsigned int entry_number_start,
    l4_utcb_t * utcb) [inline]

```

Set LDT segments descriptors.

### Parameters

<i>task</i>	Task to set the segment for.
<i>ldt</i>	Pointer to LDT hardware descriptors.
<i>num_desc</i>	Number of descriptors.
<i>entry_number_start</i>	Entry number to start.
<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. See <a href="#">l4_utcb</a> .

**Return values**

<code>-L4_ENOSYS</code>	The kernel configuration doesn't support this feature.
<code>-L4_EINVAL</code>	Invalid descriptor or invalid entry number.
<code>L4_EOK</code>	Success.


**Note**

This feature is not available if the kernel is configured with page table isolation.

Definition at line 153 of file [segment.h](#).

References [L4\\_EINVAL](#), [l4\\_ipc\\_call\(\)](#), [L4\\_IPC\\_NEVER](#), [l4\\_msgtag\(\)](#), [L4\\_PROTO\\_TASK](#), [L4\\_TASK\\_LDT\\_SET\\_X86\\_OP](#), [L4\\_TASK\\_LDT\\_X86\\_ENTRY\\_SIZE](#), and [L4\\_TASK\\_LDT\\_X86\\_MAX\\_ENTRIES](#).

Here is the call graph for this function:

**13.1.3.3 Kernel Debugger**

Kernel debugger related functionality.

Collaboration diagram for Kernel Debugger:

**Files**

- file [kdebug.h](#)

*Functionality for invoking the kernel debugger.*

## Functions

- `l4_msgtag_t l4_debugger_set_object_name (l4_cap_idx_t cap, const char *name) L4_NOTHROW`  
*Set the name of a kernel object.*
- `l4_msgtag_t l4_debugger_query_object_name (l4_cap_idx_t cap, unsigned id, char *name, unsigned size) L4_NOTHROW`  
*Get name of the kernel object with id `id`.*
- `l4_msgtag_t l4_debugger_get_object_name (l4_cap_idx_t cap, char *name, unsigned size) L4_NOTHROW`  
*Get name of a kernel object.*
- `unsigned long l4_debugger_global_id (l4_cap_idx_t cap) L4_NOTHROW`  
*Get the globally unique ID of the object behind a capability.*
- `unsigned long l4_debugger_kobj_to_id (l4_cap_idx_t cap, l4_addr_t kobjp) L4_NOTHROW`  
*Get the globally unique ID of the object behind the kobject pointer.*
- `l4_ret_t l4_debugger_query_log_typeid (l4_cap_idx_t cap, const char *name, unsigned idx) L4_NOTHROW`  
*Query the log-id for a log type.*
- `l4_ret_t l4_debugger_query_log_name (l4_cap_idx_t cap, unsigned idx, char *name, unsigned namelen, char *shortname, unsigned shortnamelen) L4_NOTHROW`  
*Query the name of a log type given the ID.*
- `l4_msgtag_t l4_debugger_switch_log (l4_cap_idx_t cap, const char *name, int on_off) L4_NOTHROW`  
*Set or unset log.*
- `l4_msgtag_t l4_debugger_add_image_info (l4_cap_idx_t cap, l4_addr_t base, const char *name) L4_NOTHROW`  
*Add loaded image information for a task.*

### 13.1.3.3.1 Detailed Description

Kernel debugger related functionality.

#### Attention

This API is subject to change!

This is a debugging facility, any call to any function might be invalid. Do not rely on it in any real code.

#### Include File

```
#include <l4/sys/debugger.h>
```

### 13.1.3.3.2 Function Documentation

#### 13.1.3.3.2.1 l4\_debugger\_add\_image\_info()

```
l4_msgtag_t l4_debugger_add_image_info (
    l4_cap_idx_t cap,
    l4_addr_t base,
    const char * name) [inline]
```

Add loaded image information for a task.



**Parameters**


<i>cap</i>	Capability which refers to the task object.
<i>base</i>	Load base address of image.
<i>name</i>	Image base name.

This is a debugging facility, the call might be invalid.

Definition at line 472 of file [debugger.h](#).

References [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:

**13.1.3.3.2.2 l4\_debugger\_get\_object\_name()**

```

l4_msgtag_t l4_debugger_get_object_name (
    l4_cap_idx_t cap,
    char * name,
    unsigned size) [inline]
  
```

Get name of a kernel object.

**Parameters**

	<i>cap</i>	Capability which refers to the kernel object.
out	<i>name</i>	<a href="#">Buffer</a> to copy the name into. The buffer must be allocated by the caller.
	<i>size</i>	Length of the <i>name</i> buffer.

**Returns**

Syscall return tag

Definition at line 465 of file [debugger.h](#).

References [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:



#### 13.1.3.3.2.3 l4\_debugger\_global\_id()

```
unsigned long l4_debugger_global_id (
    l4_cap_idx_t cap) [inline]
```

Get the globally unique ID of the object behind a capability.

##### Parameters

<i>cap</i>	Capability
------------	------------

##### Return values


<i>~0UL</i>	Capability is not valid.
<i>otherwise</i>	Global debugger id.

This is a debugging facility, the call might be invalid.

Definition at line 423 of file [debugger.h](#).

References [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:



#### 13.1.3.3.2.4 l4\_debugger\_kobj\_to\_id()

```
unsigned long l4_debugger_kobj_to_id (  
    l4_cap_idx_t cap,  
    l4_addr_t kobjp) [inline]
```

Get the globally unique ID of the object behind the kobject pointer.

##### Parameters

<i>cap</i>	Capability
<i>kobjp</i>	Kobject pointer

##### Return values


<i>~0UL</i>	The capability or the kobject pointer are invalid.
<i>otherwise</i>	The globally unique id.

This is a debugging facility, the call might be invalid.

Definition at line 429 of file [debugger.h](#).

References [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:



#### 13.1.3.3.2.5 l4\_debugger\_query\_log\_name()

```
l4_ret_t l4_debugger_query_log_name (  
    l4_cap_idx_t cap,  
    unsigned idx,  
    char * name,  
    unsigned namelen,  
    char * shortname,  
    unsigned shortnamelen) [inline]
```

Query the name of a log type given the ID.

**Parameters**

<i>cap</i>	Debugger capability.
<i>idx</i>	ID to query.
<i>name</i>	<a href="#">Buffer</a> to copy name to.
<i>namelen</i>	<a href="#">Buffer</a> length of name.
<i>shortname</i>	<a href="#">Buffer</a> to copy <code>shortname</code> to.
<i>shortnamelen</i>	<a href="#">Buffer</a> length of <code>shortname</code> .

**Return values**


<i>0</i>	Success
<i>&lt;0</i>	Error

This is a debugging facility, the call might be invalid.

Definition at line 442 of file [debugger.h](#).

References [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:

**13.1.3.3.2.6 l4\_debugger\_query\_log\_typeid()**

```

l4_ret_t l4_debugger_query_log_typeid (
    l4_cap_idx_t cap,
    const char * name,
    unsigned idx) [inline]
  
```

Query the log-id for a log type.

**Parameters**

<i>cap</i>	Debugger capability
<i>name</i>	Name to query for.
<i>idx</i>	Idx to start searching, start with 0

**Returns**


positive ID, or negative error code

This is a debugging facility, the call might be invalid.

Definition at line 435 of file [debugger.h](#).

References [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:

**13.1.3.3.2.7 l4\_debugger\_query\_object\_name()**

```

l4_msgtag_t l4_debugger_query_object_name (
    l4_cap_idx_t cap,
    unsigned id,
    char * name,
    unsigned size) [inline]
  
```

Get name of the kernel object with Id *id*.

**Parameters**

	<i>cap</i>	Capability of the debugger object.
	<i>id</i>	Global id of the object whose name is asked.
out	<i>name</i>	<a href="#">Buffer</a> to copy the name into. The buffer must be allocated by the caller.
	<i>size</i>	Length of the <i>name</i> buffer.

**Returns**

Syscall return tag

Definition at line 458 of file [debugger.h](#).

References [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:



#### 13.1.3.3.2.8 l4\_debugger\_set\_object\_name()

```
l4_msgtag_t l4_debugger_set_object_name (  
    l4_cap_idx_t cap,  
    const char * name) [inline]
```

Set the name of a kernel object.

##### Parameters

<i>cap</i>	Capability which refers to the kernel object.
<i>name</i>	Name of the kernel object that is e.g. displayed in the kernel debugger.

This is a debugging facility, the call might be invalid.

##### Examples

[examples/libs/shmc/prodcons.c](#), and [examples/sys/aliens/main.c](#).

Definition at line 416 of file [debugger.h](#).

References [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:



#### 13.1.3.3.2.9 l4\_debugger\_switch\_log()

```
l4_msgtag_t l4_debugger_switch_log (  
    l4_cap_idx_t cap,  
    const char * name,  
    int on_off) [inline]
```

Set or unset log.

##### Parameters

<i>cap</i>	Debugger object.
<i>name</i>	Name of the log type.
<i>on_off</i>	1: turn log on, 0: turn log off


##### Returns

Syscall return tag

Definition at line 451 of file [debugger.h](#).

References [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:



#### 13.1.3.4 Kernel Information Dump

Kernel information dumping related functionality.

Collaboration diagram for Kernel Information Dump:



Kernel information dumping related functionality.

Functions that dump various kernel internal information to the console. Probably only present in kernel debug builds.


##### Include File

```
#include <l4/sys/kdump.h>
```

### 13.1.3.5 Kernel Tracing

Kernel tracing related functionality.

Collaboration diagram for Kernel Tracing:



#### Functions

- `l4_umword_t fiasco_tbuf_log` (const char \*text)  
*Create new trace-buffer entry with describing <text>.*
- `l4_umword_t fiasco_tbuf_log_3val` (const char \*text, `l4_umword_t` v1, `l4_umword_t` v2, `l4_umword_t` v3)  
*Create new trace-buffer entry with describing <text> and three additional values.*
- `l4_umword_t fiasco_tbuf_log_binary` (const unsigned char \*data)  
*Create new trace-buffer entry with binary data.*
- void `fiasco_tbuf_clear` (void)  
*Clear trace-buffer.*
- void `fiasco_tbuf_dump` (void)  
*Dump trace-buffer to kernel console.*

#### 13.1.3.5.1 Detailed Description

Kernel tracing related functionality.

##### Attention

This API is subject to change!

This is a tracing facility for the Fiasco kernel trace buffer. Any call to any function might be invalid. Do not rely on it in any real code.

##### Include File

```
#include <l4/sys/ktrace.h>
```



### 13.1.3.5.2 Function Documentation

#### 13.1.3.5.2.1 fiasco\_tbuf\_log()

```
l4_umword_t fiasco_tbuf_log (
    const char * text) [inline]
```

Create new trace-buffer entry with describing <text>.

##### Parameters

<i>text</i>	Logging text
-------------	--------------


##### Returns

Pointer to trace-buffer entry

Definition at line 24 of file [\\_\\_ktrace-impl.h](#).

References [\\_\\_l4\\_kdebug\\_text\(\)](#), and [l4\\_error\(\)](#).

Here is the call graph for this function:



#### 13.1.3.5.2.2 fiasco\_tbuf\_log\_3val()

```
l4_umword_t fiasco_tbuf_log_3val (
    const char * text,
    l4_umword_t v1,
    l4_umword_t v2,
    l4_umword_t v3) [inline]
```

Create new trace-buffer entry with describing <text> and three additional values.

##### Parameters

<i>text</i>	Logging text
-------------	--------------

<i>v1</i>	first value
<i>v2</i>	second value
<i>v3</i>	third value


**Returns**

Pointer to trace-buffer entry

Definition at line 31 of file [\\_\\_ktrace-impl.h](#).

References [\\_\\_l4\\_kdebug\\_3\\_text\(\)](#), and [l4\\_error\(\)](#).

Here is the call graph for this function:

**13.1.3.5.2.3 fiasco\_tbuf\_log\_binary()**

```
l4_umword_t fiasco_tbuf_log_binary (
    const unsigned char * data) [inline]
```

Create new trace-buffer entry with binary data.

**Parameters**

<i>data</i>	binary data
-------------	-------------


**Returns**

Pointer to trace-buffer entry

Definition at line 54 of file [\\_\\_ktrace-impl.h](#).

References [\\_\\_l4\\_kdebug\\_text\(\)](#), and [l4\\_error\(\)](#).

Here is the call graph for this function:



### 13.1.4 Flexpages

Flexpage-related API.

Collaboration diagram for Flexpages:



#### Data Structures

- union [l4\\_fpage\\_t](#)  
*L4 flexpage type.*

#### Enumerations

- enum [L4\\_fpage\\_consts](#) {  
[L4\\_FPAGE\\_RIGHTS\\_SHIFT](#) = 0 , [L4\\_FPAGE\\_TYPE\\_SHIFT](#) = 4 , [L4\\_FPAGE\\_SIZE\\_SHIFT](#) = 6 ,  
[L4\\_FPAGE\\_ADDR\\_SHIFT](#) = 12 ,  
[L4\\_FPAGE\\_RIGHTS\\_BITS](#) = 4 , [L4\\_FPAGE\\_TYPE\\_BITS](#) = 2 , [L4\\_FPAGE\\_SIZE\\_BITS](#) = 6 , [L4\\_FPAGE\\_ADDR\\_BITS](#)  
= [L4\\_MWORD\\_BITS](#) - [L4\\_FPAGE\\_ADDR\\_SHIFT](#) ,  
[L4\\_FPAGE\\_RIGHTS\\_MASK](#) , [L4\\_FPAGE\\_TYPE\\_MASK](#) , [L4\\_FPAGE\\_SIZE\\_MASK](#) , [L4\\_FPAGE\\_ADDR\\_](#)  
[\\_MASK](#) = ~0UL << [L4\\_FPAGE\\_ADDR\\_SHIFT](#) ,  
[L4\\_FPAGE\\_RIGHTS\\_ALL](#) = [L4\\_FPAGE\\_RIGHTS\\_MASK](#) }  
*L4 flexpage structure.*
- enum { [L4\\_WHOLE\\_ADDRESS\\_SPACE](#) = 63 }  
*Constants for flexpages.*
- enum [L4\\_fpage\\_rights](#) {  
[L4\\_FPAGE\\_X](#) = 1 , [L4\\_FPAGE\\_W](#) = 2 , [L4\\_FPAGE\\_RO](#) = 4 , [L4\\_FPAGE\\_RW](#) = [L4\\_FPAGE\\_RO](#) | [L4\\_F](#)  
[FPAGE\\_W](#) ,  
[L4\\_FPAGE\\_RX](#) = [L4\\_FPAGE\\_RO](#) | [L4\\_FPAGE\\_X](#) , [L4\\_FPAGE\\_RWX](#) = [L4\\_FPAGE\\_RW](#) | [L4\\_FPAGE\\_X](#) }

*Memory and IO port flexpage rights.*

- enum `L4_cap_fpage_rights` {  
`L4_CAP_FPAGE_W` = 0x1 , `L4_CAP_FPAGE_S` = 0x2 , `L4_CAP_FPAGE_R` = 0x4 , `L4_CAP_FPAGE_RO` = 0x4 ,  
`L4_CAP_FPAGE_D` = 0x8 , `L4_CAP_FPAGE_RW` = `L4_CAP_FPAGE_R` | `L4_CAP_FPAGE_W` ,  
`L4_CAP_FPAGE_RS` = `L4_CAP_FPAGE_R` | `L4_CAP_FPAGE_S` , `L4_CAP_FPAGE_RWS` = `L4_CAP_FPAGE_R` | `L4_CAP_FPAGE_S` | `L4_CAP_FPAGE_W` ,  
`L4_CAP_FPAGE_RWSD` = `L4_CAP_FPAGE_RWS` | `L4_CAP_FPAGE_D` , `L4_CAP_FPAGE_RWD` = `L4_CAP_FPAGE_R` | `L4_CAP_FPAGE_D` | `L4_CAP_FPAGE_W` ,  
`L4_CAP_FPAGE_RSD` = `L4_CAP_FPAGE_RS` | `L4_CAP_FPAGE_D` }

*Object flexpage rights.*

- enum `L4_fpage_type` { `L4_FPAGE_SPECIAL` = 0 , `L4_FPAGE_MEMORY` = 1 , `L4_FPAGE_IO` = 2 , `L4_FPAGE_OBJ` = 3 }

*Flexpage type.*

- enum `L4_fpage_control` { `L4_FPAGE_CONTROL_OFFSET_SHIFT` = 12 , `L4_FPAGE_CONTROL_MASK` =  $\sim 0UL \ll L4\_FPAGE\_CONTROL\_OFFSET\_SHIFT$  }

*Flexpage map control flags.*

- enum { `L4_WHOLE_IOADDRESS_SPACE` = 16 , `L4_IOPORT_MAX` =  $(1L \ll L4\_WHOLE\_IOADDRESS\_SPACE)$  }

*Special constants for IO flexpages.*

## Functions

- `l4_fpage_t l4_fpage(l4_addr_t address, unsigned int order, unsigned char rights)` `L4_NOTHROW`  
*Create a memory flexpage.*
- `l4_fpage_t l4_fpage_all(void)` `L4_NOTHROW`  
*Get a flexpage, describing all address spaces at once.*
- `l4_fpage_t l4_fpage_invalid(void)` `L4_NOTHROW`  
*Get an invalid flexpage.*
- `l4_fpage_t l4_iofpage(unsigned long port, unsigned int order)` `L4_NOTHROW`  
*Create an IO-port flexpage.*
- `l4_fpage_t l4_obj_fpage(l4_cap_idx_t obj, unsigned int order, unsigned char rights)` `L4_NOTHROW`  
*Create a kernel-object flexpage.*
- int `l4_is_fpage_writable(l4_fpage_t fp)` `L4_NOTHROW`  
*Test if the flexpage is writable.*
- unsigned `l4_fpage_rights(l4_fpage_t f)` `L4_NOTHROW`  
*Return rights from a flexpage.*
- unsigned `l4_fpage_type(l4_fpage_t f)` `L4_NOTHROW`  
*Return type from a flexpage.*
- unsigned `l4_fpage_size(l4_fpage_t f)` `L4_NOTHROW`  
*Return size (log2) from a flexpage.*
- unsigned long `l4_fpage_page(l4_fpage_t f)` `L4_NOTHROW`  
*Return the page part from a flexpage.*
- `l4_addr_t l4_fpage_memaddr(l4_fpage_t f)` `L4_NOTHROW`  
*Return the memory address from the memory flexpage.*
- `l4_cap_idx_t l4_fpage_obj(l4_fpage_t f)` `L4_NOTHROW`  
*Return the capability index from the object flexpage.*
- unsigned long `l4_fpage_ioport(l4_fpage_t f)` `L4_NOTHROW`  
*Return the IO port number from the IO flexpage.*
- `l4_fpage_t l4_fpage_set_rights(l4_fpage_t src, unsigned char new_rights)` `L4_NOTHROW`  
*Set new right in a flexpage.*
- int `l4_fpage_contains(l4_fpage_t fpage, l4_addr_t addr, unsigned order)` `L4_NOTHROW`

*Test whether a given range is completely within an fpage.*

- unsigned char [l4\\_fpage\\_max\\_order](#) (unsigned char order, [l4\\_addr\\_t](#) addr, [l4\\_addr\\_t](#) min\_addr, [l4\\_addr\\_t](#) max\_addr, [l4\\_addr\\_t](#) hotspot=0)

*Determine maximum flexpage size of a region.*

- int [l4\\_is\\_fpage\\_valid](#) ([l4\\_fpage\\_t](#) fp) [L4\\_NOTHROW](#)

*Test if the flexpage is valid.*

#### 13.1.4.1 Detailed Description

Flexpage-related API.

A flexpage is a page with a variable size, that can describe memory, IO-Ports (IA32 only), and sets of kernel objects.

A flexpage describes an always size aligned region of an address space. The size is given in a log2 scale. This means the size in elements (bytes for memory, ports for IO-Ports, and capabilities for kernel objects) is always a power of two.

A flexpage also carries type and access right information for the described region. The type information selects the address space in which the flexpage is valid. Access rights have a meaning depending on the specific address space (type).

There exists a special type for defining *receive windows* or for the [l4\\_task\\_unmap\(\)](#) method, that can be used to describe all address spaces (all types) with a single flexpage.

##### Include File

```
#include <l4/sys/types.h>
```

#### 13.1.4.2 Enumeration Type Documentation

##### 13.1.4.2.1 anonymous enum

anonymous enum

Constants for flexpages.

##### Enumerator

<a href="#">L4_WHOLE_ADDRESS_SPACE</a>	Whole address space size. This value does not only specify the log2 size of the biggest possible memory flexpage. It can be also used as size for a special flexpage to define a flexpage which completely covers all spaces.
--	---

Definition at line 84 of file [\\_\\_l4\\_fpage.h](#).

### 13.1.4.2.2 anonymous enum

`anonymous enum`

Special constants for IO flexpages.

#### Enumerator

L4_WHOLE_IOADDRESS_SPACE	Whole I/O address space size. In contrast to <a href="#">L4_WHOLE_ADDRESS_SPACE</a> , this value forms the log2 size of the biggest possible I/O flexpage.
L4_IOPORT_MAX	Maximum I/O port address plus 1.

Definition at line 326 of file [\\_\\_l4\\_fpage.h](#).

### 13.1.4.2.3 L4\_cap\_fpage\_rights

`enum L4_cap_fpage_rights`

Object flexpage rights.

Capabilities are modified or transferred with map and unmap operations. For that, capabilities are wrapped into flexpage objects. The flexpage carries a set of rights the sender wants to hand over to the receiver along with the capability.

For the user only the 'S' and the 'W' right are visible. Other rights such as the 'D' right are internal to the corresponding kernel object and cannot be evaluated by the receiver.

Note that additional object attributes and permissions can be specified in a send item, see [Attributes and additional permissions for objects](#).

#### Note

A thread can also map a capability from its task's capability table with a reduced set of rights into another slot of its own capability table.

#### Enumerator

L4_CAP_FPAGE_W	Interface specific 'W' right for capability flexpages. The semantics of the 'W' right is defined by the protocol. For example in case of a dataspace cap, the 'W' right is needed to get a writable dataspace.
L4_CAP_FPAGE_S	Interface specific 'S' right for capability flexpages. The semantics of the 'S' right is defined by the interface. When transferring object capabilities via IPC, the kernel masks this right with the 'S' right of the capability used to address the IPC partner. Thus, the 'S' right of sent capabilities is only transferred if both the flexpage and the IPC gate or thread capability specifying the IPC partner have the 'S' right. For <a href="#">L4::Task::map()</a> , the 'S' right is only transferred if the flexpage, the source and destination task capabilities have the 'S' right.
L4_CAP_FPAGE_R	Read right for capability flexpages. This is always required, otherwise no capability is mapped.
L4_CAP_FPAGE_RO	Read right for capability flexpages. This is always required, otherwise no capability is mapped.

L4_CAP_FPAGE_D	Delete right for capability flexpages. This allows the receiver to delete the corresponding kernel object using <code>unmap()</code> regardless of other tasks still holding a capability to the kernel object. Such capabilities are set to an empty capability if the object is deleted.
L4_CAP_FPAGE_RW	Read and interface specific 'W' right for capability flexpages. The semantics of the 'W' right is defined by the interface.  See also <a href="#">L4_CAP_FPAGE_W</a>
L4_CAP_FPAGE_RS	Read and interface specific 'S' right for capability flexpages. The semantics of the 'S' right is defined by the interface.  See also <a href="#">L4_CAP_FPAGE_S</a>
L4_CAP_FPAGE_RWS	Read, interface specific 'W', and 'S' rights for capability flexpages. The semantics of the 'W' and 'S' right are defined by the interface.  See also <a href="#">L4_CAP_FPAGE_R</a> , <a href="#">L4_CAP_FPAGE_W</a> , and <a href="#">L4_CAP_FPAGE_S</a>
L4_CAP_FPAGE_RWSD	Full rights for capability flexpages.  See also <a href="#">L4_CAP_FPAGE_R</a> , <a href="#">L4_CAP_FPAGE_W</a> , <a href="#">L4_CAP_FPAGE_S</a> , and <a href="#">L4_CAP_FPAGE_D</a>
L4_CAP_FPAGE_RWD	Read, write, and delete right for capability flexpages.  See also <a href="#">L4_CAP_FPAGE_R</a> , <a href="#">L4_CAP_FPAGE_W</a> , and <a href="#">L4_CAP_FPAGE_D</a>
L4_CAP_FPAGE_RSD	Read, 'S', and delete right for capability flexpages.  See also <a href="#">L4_CAP_FPAGE_R</a> , <a href="#">L4_CAP_FPAGE_S</a> , and <a href="#">L4_CAP_FPAGE_D</a>

Definition at line 148 of file [\\_\\_l4\\_fpage.h](#).

#### 13.1.4.2.4 L4\_fpage\_consts

enum [L4\\_fpage\\_consts](#)

[L4](#) flexpage structure.

##### Enumerator

L4_FPAGE_RIGHTS_SHIFT	Access permissions shift.
L4_FPAGE_TYPE_SHIFT	Flexpage type shift (memory, IO port, obj...).

L4_FPAGE_SIZE_SHIFT	Flexpage size shift (log2-based).
L4_FPAGE_ADDR_SHIFT	Page address shift.
L4_FPAGE_RIGHTS_BITS	Access permissions size.
L4_FPAGE_TYPE_BITS	Flexpage type size (memory, IO port, obj...).
L4_FPAGE_SIZE_BITS	Flexpage size size (log2-based).
L4_FPAGE_ADDR_BITS	Page address size.
L4_FPAGE_RIGHTS_MASK	Mask to get the flexpage rights.
L4_FPAGE_RIGHTS_ALL	Specify as flexpage rights during grant.

Definition at line 48 of file [\\_\\_l4\\_fpage.h](#).

#### 13.1.4.2.5 L4\_fpage\_control

```
enum L4_fpage_control
```

Flexpage map control flags.

##### Enumerator

L4_FPAGE_CONTROL_OFFSET_SHIFT	Number of bits an index must be shifted or an address must be aligned to in the control word.
L4_FPAGE_CONTROL_MASK	Mask for truncating the lower bits of the send base or the index of the control word.

Definition at line 243 of file [\\_\\_l4\\_fpage.h](#).

#### 13.1.4.2.6 L4\_fpage\_rights

```
enum L4_fpage_rights
```

Memory and IO port flexpage rights.

For IO flexpages, bit 1 and bit 2 are a combined read/write right. In a map operation, the receiver receives the IO port capability when the sender possesses it and at least one of these bits is present. For an unmap operation, the absence of one of those bits is sufficient to unmap the IO port capability.

Note that more memory attributes can be specified in a send item, see [l4\\_fpage\\_cacheability\\_opt\\_t](#).

##### Enumerator

L4_FPAGE_X	Executable flexpage.
L4_FPAGE_W	Writable flexpage.
L4_FPAGE_RO	Read-only flexpage.
L4_FPAGE_RW	Read-write flexpage.



L4_FPAGE_RX	Read-execute flexpage.
L4_FPAGE_RWX	Read-write-execute flexpage.

Definition at line 118 of file [\\_\\_l4\\_fpage.h](#).

#### 13.1.4.2.7 L4\_fpage\_type

enum [L4\\_fpage\\_type](#)

Flexpage type.

##### Enumerator

L4_FPAGE_SPECIAL	Special flexpage, either <a href="#">l4_fpage_invalid()</a> or <a href="#">l4_fpage_all()</a> ; only supported by selected interfaces.
L4_FPAGE_MEMORY	Flexpage for memory spaces.
L4_FPAGE_IO	Flexpage for I/O port spaces.
L4_FPAGE_OBJ	Flexpage for object spaces.

Definition at line 230 of file [\\_\\_l4\\_fpage.h](#).

#### 13.1.4.3 Function Documentation

##### 13.1.4.3.1 l4\_fpage()

```
l4_fpage_t l4_fpage (
    l4_addr_t address,
    unsigned int order,
    unsigned char rights) [inline]
```

Create a memory flexpage.

##### Parameters

<i>address</i>	Flexpage start address
<i>order</i>	Flexpage size (log2), <a href="#">L4_WHOLE_ADDRESS_SPACE</a> to specify the whole address space (with address 0). The minimum log2 size of a memory flexpage is defined by <a href="#">L4_LOG2_PAGESIZE</a> according to the size of the smallest virtual page supported by the MMU.
<i>rights</i>	Access rights, see <a href="#">L4_fpage_rights</a>

**Returns**


Memory flexpage

Definition at line 715 of file [\\_\\_l4\\_fpage.h](#).

References [L4\\_FPAGE\\_MEMORY](#), and [L4\\_NOTHROW](#).

Referenced by [L4Re::Util::Dataspace\\_svr::map\(\)](#), [L4::lpc::Rcv\\_fpage::mem\(\)](#), and [L4::lpc::Snd\\_fpage::mem\(\)](#).

Here is the caller graph for this function:

**13.1.4.3.2 l4\_fpage\_all()**

```
l4_fpage_t l4_fpage_all (
    void ) [inline]
```

Get a flexpage, describing all address spaces at once.

**Returns**

Special *all-spaces* flexpage.

**Note**

This flexpage can be used to define a receive window where the sender can send objects of any type, or for an unmap item completely covering all spaces of the target task. It does not make sense to use this flexpage as send item.

Definition at line 735 of file [\\_\\_l4\\_fpage.h](#).

References [L4\\_FPAGE\\_SPECIAL](#), [L4\\_NOTHROW](#), and [L4\\_WHOLE\\_ADDRESS\\_SPACE](#).

#### 13.1.4.3.3 l4\_fpage\_contains()

```
int l4_fpage_contains (
    l4_fpage_t fpage,
    l4_addr_t addr,
    unsigned order) [inline]
```

Test whether a given range is completely within an fpage.

##### Parameters

<i>fpage</i>	Flexpage
<i>addr</i>	Address
<i>order</i>	Size of range in log2.


##### Return values

<code>==0</code>	The range is not completely in the fpage.
<code>!=0</code>	The range is within the fpage.

Definition at line 767 of file [\\_\\_l4\\_fpage.h](#).

References [l4\\_fpage\\_memaddr\(\)](#), [l4\\_fpage\\_size\(\)](#), and [L4\\_NOTHROW](#).

Here is the call graph for this function:



#### 13.1.4.3.4 l4\_fpage\_invalid()

```
l4_fpage_t l4_fpage_invalid (
    void ) [inline]
```

Get an invalid flexpage.

##### Returns

Special *invalid* flexpage.

Definition at line 741 of file [\\_\\_l4\\_fpage.h](#).

References [L4\\_FPAGE\\_SPECIAL](#), and [L4\\_NOTHROW](#).

#### 13.1.4.3.5 l4\_fpage\_ioport()

```
unsigned long l4_fpage_ioport (
    l4_fpage_t f) [inline]
```

Return the IO port number from the IO flexpage.

##### Parameters

<i>f</i>	Flexpage
----------	----------

##### Returns

IO port number from the given IO flexpage.

##### Precondition

*f* must be an IO flexpage (`l4_fpage_type(f) == L4_FPAGE_IO`) and

The function does not enforce size alignment of the read memory address. The caller must ensure the input fpage is correct.

Definition at line 671 of file `__l4_fpage.h`.

References `L4_FPAGE_ADDR_SHIFT`, and `L4_NOTHROW`.

#### 13.1.4.3.6 l4\_fpage\_max\_order()

```
unsigned char l4_fpage_max_order (
    unsigned char order,
    l4_addr_t addr,
    l4_addr_t min_addr,
    l4_addr_t max_addr,
    l4_addr_t hotspot = 0) [inline]
```

Determine maximum flexpage size of a region.

##### Parameters

<i>order</i>	Order value to start with (e.g. for memory <code>L4_LOG2_PAGESIZE</code> would be used)
<i>addr</i>	Address to be covered by the flexpage.
<i>min_addr</i>	Start of region / minimal address (including).
<i>max_addr</i>	End of region / maximal address (excluding).
<i>hotspot</i>	(Optional) hot spot.

##### Returns

Maximum order (log2-size) possible.


**Note**

The start address of the flexpage can be determined with `l4_trunc_size(addr, returnvalue)`

Definition at line 775 of file `__l4_fpage.h`.

References `l4_trunc_size()`.

Here is the call graph for this function:

**13.1.4.3.7 l4\_fpage\_memaddr()**

```
l4_addr_t l4_fpage_memaddr (
    l4_fpage_t f) [inline]
```

Return the memory address from the memory flexpage.

**Parameters**

<i>f</i>	Flexpage
----------	----------

**Returns**

Page address from the given memory flexpage.

**Precondition**

*f* must be a memory flexpage (`l4_fpage_type(f) == L4_FPAGE_MEMORY`).

The function does not enforce size alignment of the read memory address. The caller must ensure the input *fpage* is correct.

Definition at line 677 of file `__l4_fpage.h`.

References `L4_NOTHROW`.

Referenced by `l4_fpage_contains()`.

Here is the caller graph for this function:



#### 13.1.4.3.8 l4\_fpage\_obj()

```
l4_cap_idx_t l4_fpage_obj (
    l4_fpage_t f) [inline]
```

Return the capability index from the object flexpage.

##### Parameters

<i>f</i>	Flexpage
----------	----------

##### Returns

Capability index from the given object flexpage.

##### Precondition

*f* must be an object flexpage (`l4_fpage_type(f) == L4_FPAGE_OBJ`)

The function does not enforce size alignment of the read memory address. The caller must ensure the input fpage is correct.

Definition at line 683 of file [\\_\\_l4\\_fpage.h](#).

References [L4\\_NOTHROW](#).

#### 13.1.4.3.9 l4\_fpage\_page()

```
unsigned long l4_fpage_page (
    l4_fpage_t f) [inline]
```

Return the page part from a flexpage.

##### Parameters

<i>f</i>	Flexpage
----------	----------

##### Returns

Page part of the given flexpage.

##### Note

The meaning of the page part depends on the flexpage type.

Definition at line 665 of file [\\_\\_l4\\_fpage.h](#).

References [L4\\_FPAGE\\_ADDR\\_SHIFT](#), and [L4\\_NOTHROW](#).

#### 13.1.4.3.10 l4\_fpage\_rights()

```
unsigned l4_fpage_rights (  
    l4_fpage_t f) [inline]
```

Return rights from a flexpage.

##### Parameters

<i>f</i>	Flexpage
----------	----------

##### Returns

Size part of the given flexpage.

Definition at line 647 of file `__l4_fpage.h`.

References `L4_FPAGE_RIGHTS_MASK`, `L4_FPAGE_RIGHTS_SHIFT`, and `L4_NOTHROW`.

Referenced by `l4_is_fpage_writable()`.

Here is the caller graph for this function:



#### 13.1.4.3.11 l4\_fpage\_set\_rights()

```
l4_fpage_t l4_fpage_set_rights (  
    l4_fpage_t src,  
    unsigned char new_rights) [inline]
```

Set new right in a flexpage.

##### Parameters

<i>src</i>	Flexpage
<i>new_rights</i>	New rights

**Returns**

Modified flexpage with new rights.

Definition at line 706 of file [\\_\\_l4\\_fpage.h](#).

References [L4\\_FPAGE\\_RIGHTS\\_MASK](#), [L4\\_FPAGE\\_RIGHTS\\_SHIFT](#), [L4\\_NOTHROW](#), and [l4\\_fpage\\_t::raw](#).

Referenced by [L4::lpc::Snd\\_fpage::io\(\)](#).

Here is the caller graph for this function:

**13.1.4.3.12 l4\_fpage\_size()**

```
unsigned l4_fpage_size (
    l4_fpage_t f) [inline]
```

Return size (log2) from a flexpage.

**Parameters**

<i>f</i>	Flexpage
----------	----------

**Returns**

Size part of the given flexpage.

**See also**

[l4\\_fpage\\_memaddr\(\)](#), [l4\\_fpage\\_obj\(\)](#), [l4\\_fpage\\_ioport\(\)](#)


Definition at line 659 of file [\\_\\_l4\\_fpage.h](#).

References [L4\\_FPAGE\\_SIZE\\_SHIFT](#), and [L4\\_NOTHROW](#).

Referenced by [l4\\_fpage\\_contains\(\)](#), and [l4\\_is\\_fpage\\_valid\(\)](#).



Here is the caller graph for this function:



#### 13.1.4.3.13 `l4_fpage_type()`

```
unsigned l4_fpage_type (
    l4_fpage_t f) [inline]
```

Return type from a flexpage.

##### Parameters

<i>f</i>	Flexpage
----------	----------

##### Returns

Type part of the given flexpage.

Definition at line 653 of file `__l4_fpage.h`.

References `L4_FPAGE_TYPE_SHIFT`, and `L4_NOTHROW`.

Referenced by `l4_is_fpage_valid()`.

Here is the caller graph for this function:



#### 13.1.4.3.14 l4\_iofpage()

```
l4_fpage_t l4_iofpage (
    unsigned long port,
    unsigned int order) [inline]
```

Create an IO-port flexpage.

##### Parameters

<i>port</i>	I/O-flexpage port base
<i>order</i>	I/O-flexpage size (log2), <a href="#">L4_WHOLE_IOADDRESS_SPACE</a> to specify the whole I/O address space (with <code>port 0</code> )

##### Returns


I/O flexpage

Definition at line 721 of file [\\_\\_l4\\_fpage.h](#).

References [L4\\_FPAGE\\_ADDR\\_SHIFT](#), [L4\\_FPAGE\\_IO](#), [L4\\_FPAGE\\_RW](#), and [L4\\_NOTHROW](#).

Referenced by [L4::lpc::Rcv\\_fpage::io\(\)](#), [L4::lpc::Snd\\_fpage::io\(\)](#), and [l4util\\_ioport\\_map\(\)](#).

Here is the caller graph for this function:



#### 13.1.4.3.15 l4\_is\_fpage\_valid()

```
int l4_is_fpage_valid (
    l4_fpage_t fp) [inline]
```

Test if the flexpage is valid.

**Parameters**

<i>fp</i>	Flexpage.
-----------	-----------


**Return values**

<i>!=0</i>	if flexpage is valid.
<i>==0</i>	if flexpage is not valid.

Definition at line 800 of file [\\_\\_l4\\_fpage.h](#).

References [l4\\_fpage\\_size\(\)](#), [L4\\_FPAGE\\_SPECIAL](#), [l4\\_fpage\\_type\(\)](#), and [L4\\_NOTHROW](#).

Here is the call graph for this function:

**13.1.4.3.16 l4\_is\_fpage\_writable()**

```
int l4_is_fpage_writable (
    l4_fpage_t fp) [inline]
```

Test if the flexpage is writable.

**Parameters**

<i>fp</i>	Flexpage.
-----------	-----------


**Return values**

<i>!=0</i>	if flexpage is writable.
<i>==0</i>	if flexpage is not writable.

Definition at line 748 of file [\\_\\_l4\\_fpage.h](#).

References [l4\\_fpage\\_rights\(\)](#), [L4\\_FPAGE\\_W](#), and [L4\\_NOTHROW](#).

Here is the call graph for this function:



### 13.1.4.3.17 l4\_obj\_fpage()

```

l4_fpage_t l4_obj_fpage (
    l4_cap_idx_t obj,
    unsigned int order,
    unsigned char rights) [inline]
  
```

Create a kernel-object flexpage.

#### Parameters

<i>obj</i>	Base capability selector.
<i>order</i>	Log2 size (number of capabilities).
<i>rights</i>	Access rights, see <a href="#">L4_cap_fpage_rights</a>

#### Returns

Flexpage for a set of kernel objects.

#### Note

[L4\\_CAP\\_FPAGE\\_R](#) is always required, otherwise no capability is mapped.

#### Examples


[examples/sys/utcb-ipc/main.c](#).

Definition at line 727 of file [\\_\\_l4\\_fpage.h](#).

References [L4\\_CAP\\_SHIFT](#), [L4\\_FPAGE\\_ADDR\\_SHIFT](#), [L4\\_FPAGE\\_OBJ](#), and [L4\\_NOTHROW](#).

Referenced by [L4::Cap\\_base::fpage\(\)](#), [l4\\_icu\\_bind\\_u\(\)](#), [l4\\_icu\\_unbind\\_u\(\)](#), [l4\\_irq\\_bind\\_vcpu\\_u\(\)](#), [L4::lpc::Rcv\\_fpage::obj\(\)](#), and [L4::lpc::Snd\\_fpage::obj\(\)](#).


Here is the caller graph for this function:



### 13.1.5 C++ IPC Interface Definition

APIs for defining IPC interfaces using C++ as language.

Collaboration diagram for C++ IPC Interface Definition:



#### Topics

- Internal•Helpers . . . . . 192

#### Namespaces


- namespace [L4::Typeid](#)  
Definition of interface data-type helpers.

#### 13.1.5.1 Detailed Description

APIs for defining IPC interfaces using C++ as language.

### 13.1.5.2 Internal Helpers

Collaboration diagram for Internal Helpers:



## Data Structures

- struct `L4::Types::Bool< V >`  
*Boolean meta type.*
- struct `L4::Types::False`  
*False meta value.*
- struct `L4::Types::True`  
*True meta value.*
- struct `L4::Types::Same< A, B >`  
*Compare two data types for equality.*

### 13.1.5.2.1 Detailed Description

## 13.1.6 Cache Consistency

Various functions for cache consistency.

Collaboration diagram for Cache Consistency:



## Functions

- `L4_BEGIN_DECLS` `int l4_cache_clean_data` (unsigned long start, unsigned long end) `L4_NOTHROW`  
*Cache clean a range in D-cache; writes back to PoC.*
- `int l4_cache_flush_data` (unsigned long start, unsigned long end) `L4_NOTHROW`  
*Cache flush a range; writes back to PoC.*
- `int l4_cache_inv_data` (unsigned long start, unsigned long end) `L4_NOTHROW`  
*Cache invalidate a range; might write back to PoC.*
- `int l4_cache_coherent` (unsigned long start, unsigned long end) `L4_NOTHROW`  
*Make memory coherent between I-cache and D-cache; writes back to PoU.*
- `int l4_cache_dma_coherent` (unsigned long start, unsigned long end) `L4_NOTHROW`  
*Make memory coherent for use with external memory; writes back to PoC.*
- `int l4_cache_dma_coherent_full` (void) `L4_NOTHROW`  
*Make memory coherent for use with external memory; writes back to PoC.*

### 13.1.6.1 Detailed Description

Various functions for cache consistency.

These functions shall be used to ensure that

- all blocks (e.g. CPU cores, devices, DMA engines) are guaranteed to see the same copy of a memory location (Point of Coherency – PoC),
- instruction and data caches of a core are guaranteed to see the same copy of a memory location (Point of Unification – PoU).

Certain functions are NOPs on certain architectures, for example on Intel it's not necessary to explicitly make caches coherent to PoU.

### 13.1.6.2 Function Documentation

#### 13.1.6.2.1 `l4_cache_clean_data()`

```
L4_BEGIN_DECLS
int l4_cache_clean_data (
    unsigned long start,
    unsigned long end) [inline]
```

Cache clean a range in D-cache; writes back to PoC.

#### Parameters

<i>start</i>	Start of range (inclusive)
<i>end</i>	End of range (exclusive)

#### Return values

---

<i>0</i>	on success
<i>-EFAULT</i>	in the case of an unresolved page fault in the given area

Writes back any dirty cache lines in the range but leaves them in the cache and marks the cached copies clean.

#### Examples

[examples/libs/l4re/c++/shared\\_ds/ds\\_clnt.cc](#).

Definition at line 68 of file [cache.h](#).

References [L4\\_NOTHROW](#).

#### 13.1.6.2.2 l4\_cache\_coherent()

```
int l4_cache_coherent (
    unsigned long start,
    unsigned long end) [inline]
```

Make memory coherent between I-cache and D-cache; writes back to PoU.

#### Parameters

<i>start</i>	Start of range (inclusive)
<i>end</i>	End of range (exclusive)

#### Return values

<i>0</i>	on success
<i>-EFAULT</i>	in the case of an unresolved page fault in the given area

Definition at line 92 of file [cache.h](#).

References [L4\\_NOTHROW](#).

#### 13.1.6.2.3 l4\_cache\_dma\_coherent()

```
int l4_cache_dma_coherent (
    unsigned long start,
    unsigned long end) [inline]
```

Make memory coherent for use with external memory; writes back to PoC.

#### Parameters

---



<i>start</i>	Start of range (inclusive)
<i>end</i>	End of range (exclusive)

#### Return values

<i>0</i>	on success
<i>-EFAULT</i>	in the case of an unresolved page fault in the given area

Definition at line 100 of file [cache.h](#).

References [L4\\_NOTHROW](#).

#### 13.1.6.2.4 l4\_cache\_flush\_data()

```
int l4_cache_flush_data (  
    unsigned long start,  
    unsigned long end) [inline]
```

Cache flush a range; writes back to PoC.

#### Parameters

<i>start</i>	Start of range (inclusive)
<i>end</i>	End of range (exclusive)

#### Return values

<i>0</i>	on success
<i>-EFAULT</i>	in the case of an unresolved page fault in the given area

Writes back any dirty cache lines and invalidates all cache entries in the range.

Definition at line 76 of file [cache.h](#).

References [L4\\_NOTHROW](#).

#### 13.1.6.2.5 l4\_cache\_inv\_data()

```
int l4_cache_inv_data (  
    unsigned long start,  
    unsigned long end) [inline]
```

Cache invalidate a range; might write back to PoC.

**Parameters**

<i>start</i>	Start of range (inclusive)
<i>end</i>	End of range (exclusive)

**Return values**

0	on success
-EFAULT	in the case of an unresolved page fault in the given area

Invalidates all cache entries in the range but does not necessarily write back dirty cache lines.

**Note**

Implementations may choose to write back dirty lines nonetheless if this is more efficient.

Definition at line 84 of file [cache.h](#).

References [L4\\_NOTHROW](#).

**13.1.7 Memory related**

Memory related constants, data types and functions.

Collaboration diagram for Memory related:

**Macros**

- **#define L4\_PAGESIZE**  
*Minimal page size (in bytes).*
- **#define L4\_PAGEMASK**  
*Mask for the page number.*
- **#define L4\_LOG2\_PAGESIZE**  
*Number of bits used for page offset.*
- **#define L4\_SUPERPAGESIZE**  
*Size of a large page.*
- **#define L4\_SUPERPAGEMASK**  
*Mask for the number of a large page.*

- `#define L4_LOG2_SUPERPAGESIZE`  
*Number of bits used as offset for a large page.*
- `#define L4_INVALID_PTR ((void *)L4_INVALID_ADDR)`  
*Invalid address as pointer type.*
- `#define L4_PAGESHIFT 12`  
*Size of a page, log2-based.*
- `#define L4_SUPERPAGESHIFT 21`  
*Size of a large page, log2-based.*
- `#define L4_PAGESHIFT 12`  
*Size of a page, log2-based.*
- `#define L4_SUPERPAGESHIFT 21`  
*Size of a large page, log2-based.*
- `#define L4_PAGESHIFT 12`  
*Size of a page, log2-based.*
- `#define L4_SUPERPAGESHIFT 21`  
*Size of a large page, log2-based.*
- `#define L4_PAGESHIFT 12`  
*Size of a page log2-based.*
- `#define L4_SUPERPAGESHIFT 22`  
*Size of a large page log2-based.*

## Enumerations

- enum `l4_addr_consts_t` { `L4_INVALID_ADDR` = `~0UL` }  
*Address related constants.*

## Functions

- `l4_addr_t l4_trunc_page (l4_addr_t address)` `L4_NOTHROW`  
*Round an address down to the next lower page boundary.*
- `l4_addr_t l4_trunc_size (l4_addr_t address, unsigned char bits)` `L4_NOTHROW`  
*Round an address down to the next lower flexpage with size bits.*
- `l4_addr_t l4_round_page (l4_addr_t address)` `L4_NOTHROW`  
*Round address up to the next page.*
- `l4_addr_t l4_round_size (l4_addr_t value, unsigned char bits)` `L4_NOTHROW`  
*Round value up to the next alignment with bits size.*
- unsigned `l4_bytes_to_mwords` (unsigned size) `L4_NOTHROW`  
*Determine how many machine words (`l4_umword_t`) are required to store a buffer of 'size' bytes.*

### 13.1.7.1 Detailed Description

Memory related constants, data types and functions.

### 13.1.7.2 Macro Definition Documentation

#### 13.1.7.2.1 L4\_LOG2\_PAGESIZE

```
#define L4_LOG2_PAGESIZE
```

Number of bits used for page offset.

Size of page in log2.

Definition at line 407 of file [consts.h](#).

Referenced by [L4Re::Dataspace::map\(\)](#), [L4Re::Dataspace::map\\_region\(\)](#), and [L4Re::Util::Dataspace\\_svr::page\\_shift\(\)](#).

#### 13.1.7.2.2 L4\_LOG2\_SUPERPAGESIZE

```
#define L4_LOG2_SUPERPAGESIZE
```

Number of bits used as offset for a large page.

Size of large page in log2

Definition at line 433 of file [consts.h](#).

#### 13.1.7.2.3 L4\_PAGEMASK

```
#define L4_PAGEMASK
```

Mask for the page number.

##### Note

The most significant bits are set.

Definition at line 398 of file [consts.h](#).

Referenced by [L4virtio::Driver::Device::driver\\_connect\(\)](#), [l4\\_round\\_page\(\)](#), and [l4\\_trunc\\_page\(\)](#).

#### 13.1.7.2.4 L4\_PAGESHIFT [1/3]

```
#define L4_PAGESHIFT 12
```

Size of a page, log2-based.

Size of a page log2-based.

Definition at line 24 of file [consts.h](#).

#### 13.1.7.2.5 L4\_PAGESHIFT [2/3]

```
#define L4_PAGESHIFT 12
```

Size of a page, log2-based.

Size of a page log2-based.

##### Examples

[examples/libs/l4re/c++/mem\\_alloc/ma+rm.cc](#), [examples/libs/l4re/c/ma+rm.c](#), [examples/libs/l4re/streammap/client.cc](#),  
and [examples/libs/l4re/streammap/server.cc](#).

Definition at line 26 of file [consts.h](#).

Referenced by [L4Re::Rm::attach\(\)](#), [L4virtio::Driver::Device::driver\\_connect\(\)](#), [L4Re::Rm::free\\_area\(\)](#), [L4Re::Util::Dataspace\\_svr::map](#)  
[L4Re::Rm::reserve\\_area\(\)](#), [L4Re::Rm::reserve\\_area\(\)](#), [L4virtio::Driver::Block\\_device::setup\\_device\(\)](#), and  
[L4virtio::Driver::Virtio\\_net\\_device::setup\\_device\(\)](#).

#### 13.1.7.2.6 L4\_PAGESHIFT [3/3]

```
#define L4_PAGESHIFT 12
```

Size of a page, log2-based.

Size of a page log2-based.

Definition at line 26 of file [consts.h](#).

#### 13.1.7.2.7 L4\_SUPERPAGEMASK

```
#define L4_SUPERPAGEMASK
```

Mask for the number of a large page.

##### Note

The most significant bits are set.

Definition at line 425 of file [consts.h](#).

#### 13.1.7.2.8 L4\_SUPERPAGESHIFT [1/3]

```
#define L4_SUPERPAGESHIFT 21
```

Size of a large page, log2-based.

Size of a large page log2-based.

Definition at line 30 of file [consts.h](#).

**13.1.7.2.9 L4\_SUPERPAGESHIFT** [2/3]

```
#define L4_SUPERPAGESHIFT 21
```

Size of a large page, log2-based.

Size of a large page log2-based.

**Examples**

[examples/libs/l4re/c++/mem\\_alloc/ma+rm.cc](#), and [examples/libs/l4re/c/ma+rm.c](#).

Definition at line 31 of file [consts.h](#).

Referenced by [L4virtio::Svr::Driver\\_mem\\_region\\_t< No\\_custom\\_data >::Driver\\_mem\\_region\\_t\(\)](#).

**13.1.7.2.10 L4\_SUPERPAGESHIFT** [3/3]

```
#define L4_SUPERPAGESHIFT 21
```

Size of a large page, log2-based.

Size of a large page log2-based.

Definition at line 31 of file [consts.h](#).

**13.1.7.2.11 L4\_SUPERPAGESIZE**

```
#define L4_SUPERPAGESIZE
```

Size of a large page.

A large page is a *super page* on IA32 or a *section* on ARM.

Definition at line 416 of file [consts.h](#).

Referenced by [L4virtio::Driver::Device::driver\\_connect\(\)](#).

**13.1.7.3 Enumeration Type Documentation****13.1.7.3.1 l4\_addr\_consts\_t**

```
enum l4_addr_consts_t
```

Address related constants.

**Enumerator**

L4_INVALID_ADDR	Invalid address.
-----------------	------------------

Definition at line 501 of file [consts.h](#).

### 13.1.7.4 Function Documentation

#### 13.1.7.4.1 l4\_bytes\_to\_mwords()

```
unsigned l4_bytes_to_mwords (
    unsigned size) [inline]
```

Determine how many machine words ([l4\\_umword\\_t](#)) are required to store a buffer of 'size' bytes.

#### Parameters


<i>size</i>	The number of bytes to be translated into machine words.
-------------	--

Definition at line 494 of file [consts.h](#).

References [L4\\_INLINE](#), and [L4\\_NOTHROW](#).

Referenced by [\\_\\_l4\\_kdebug\\_3\\_text\(\)](#), [\\_\\_l4\\_kdebug\\_text\(\)](#), and [l4\\_vcon\\_send\\_u\(\)](#).

Here is the caller graph for this function:



#### 13.1.7.4.2 l4\_round\_page()

```
l4_addr_t l4_round_page (
    l4_addr_t address) [inline]
```

Round address up to the next page.

The address is rounded up to the next minimal page boundary. On most architectures this is a 4k page. Check [L4\\_PAGESIZE](#) for the minimal page size.

##### Parameters


<i>address</i>	The address to round up.
----------------	--------------------------

Definition at line 471 of file [consts.h](#).

References [L4\\_INLINE](#), [L4\\_NOTHROW](#), [L4\\_PAGEMASK](#), and [L4\\_PAGESIZE](#).

Referenced by [L4virtio::Svr::Driver\\_mem\\_region\\_t< No\\_custom\\_data >::Driver\\_mem\\_region\\_t\(\)](#), [L4Re::Util::Dataspace\\_svr::map\(\)](#), and [L4virtio::Driver::Block\\_device::setup\\_device\(\)](#).

Here is the caller graph for this function:



#### 13.1.7.4.3 l4\_round\_size()

```
l4_addr_t l4_round_size (
    l4_addr_t value,
    unsigned char bits) [inline]
```

Round value up to the next alignment with *bits* size.



**Parameters**


<i>value</i>	The value to round up to the next size-alignment.
<i>bits</i>	The size of the alignment (log2).

Definition at line 482 of file [consts.h](#).

References [L4\\_INLINE](#), and [L4\\_NOTHROW](#).

Referenced by [cxx::List\\_alloc::alloc\\_max\(\)](#), [L4virtio::Driver::Block\\_device::setup\\_device\(\)](#), [L4virtio::Driver::Virtio\\_net\\_device::setup\\_device\(\)](#), [L4virtio::Virtqueue::setup\\_simple\(\)](#), and [L4virtio::Virtqueue::total\\_size\(\)](#).

Here is the caller graph for this function:

**13.1.7.4.4 l4\_trunc\_page()**

```
l4_addr_t l4_trunc_page (
    l4_addr_t address) [inline]
```

Round an address down to the next lower page boundary.

The address is rounded down to the next lower minimal page boundary. On most architectures this is a 4k page. Check [L4\\_PAGESIZE](#) for the minimal page size.

**Parameters**

<i>address</i>	The address to round.
----------------	-----------------------

**Examples**


[examples/libs/l4re/c++/mem\\_alloc/ma+rm.cc](#), and [examples/libs/l4re/c/ma+rm.c](#).

Definition at line 446 of file [consts.h](#).

References [L4\\_INLINE](#), [L4\\_NOTHROW](#), and [L4\\_PAGEMASK](#).

Referenced by [L4virtio::Svr::Driver\\_mem\\_region\\_t< No\\_custom\\_data >::Driver\\_mem\\_region\\_t\(\)](#), [l4\\_touch\\_ro\(\)](#), [l4\\_touch\\_rw\(\)](#), and [L4Re::Util::Dataspace\\_svr::map\(\)](#).

Here is the caller graph for this function:



#### 13.1.7.4.5 l4\_trunc\_size()

```
l4_addr_t l4_trunc_size (
    l4_addr_t address,
    unsigned char bits) [inline]
```

Round an address down to the next lower flexpage with size *bits*.

##### Parameters


<i>address</i>	The address to round.
<i>bits</i>	The size of the flexpage (log2).

Definition at line 457 of file [consts.h](#).

References [L4\\_INLINE](#), and [L4\\_NOTHROW](#).

Referenced by [cxx::List\\_alloc::alloc\\_max\(\)](#), [l4\\_fpage\\_max\\_order\(\)](#), and [L4Re::Util::Dataspace\\_svr::map\(\)](#).

Here is the caller graph for this function:



### 13.1.8 Error codes

Common error codes.

Collaboration diagram for Error codes:



### Enumerations

- enum `l4_error_code_t` {  
`L4_EOK` = 0 , `L4_EPERM` = 1 , `L4_ENOENT` = 2 , `L4_EIO` = 5 ,  
`L4_ENXIO` = 6 , `L4_E2BIG` = 7 , `L4_EAGAIN` = 11 , `L4_ENOMEM` = 12 ,  
`L4_EACCESS` = 13 , `L4_EFAULT` = 14 , `L4_EBUSY` = 16 , `L4_EEXIST` = 17 ,  
`L4_ENODEV` = 19 , `L4_ENOTDIR` = 20 , `L4_EINVAL` = 22 , `L4_ENOSPC` = 28 ,  
`L4_ERANGE` = 34 , `L4_ENAMETOOLONG` = 36 , `L4_ENOSYS` = 38 , `L4_EBADPROTO` = 39 ,  
`L4_EADDRNOTAVAIL` = 99 , `L4_ERRNOMAX` = 100 , `L4_ENOREPLY` = 1000 , `L4_MSGTOOSHORT` = 1001 ,  
`L4_MSGTOOLONG` = 1002 , `L4_MSGMISSARG` = 1003 , `L4_MSGERRRANGE` = 1004 , `L4_EIPC_LO` = 2000 ,  
`L4_EIPC_HI` = 2000 + 0x1f }  
*L4 error codes.*

### 13.1.8.1 Detailed Description

Common error codes.

#### Include File

```
#include <l4/sys/err.h>
```

### 13.1.8.2 Enumeration Type Documentation

#### 13.1.8.2.1 l4\_error\_code\_t

```
enum l4_error_code_t
```

L4 error codes.

Those error codes are used by both the kernel and the user programs.

#### Enumerator

L4_EOK	Ok.
L4_EPERM	No permission.
L4_ENOENT	No such entity.
L4_EIO	I/O error.
L4_ENXIO	No such device or address.
L4_E2BIG	Argument value too big.
L4_EAGAIN	Try again.
L4_ENOMEM	No memory.
L4_EACCESS	Permission denied.
L4_EFAULT	Invalid memory address.
L4_EBUSY	Object currently busy, try later.
L4_EEXIST	Already exists.
L4_ENODEV	No such thing.
L4_ENOTDIR	Not a directory.
L4_EINVAL	Invalid argument.
L4_ENOSPC	No space left on device.
L4_ERANGE	Range error.
L4_ENAMETOOLONG	Name too long.
L4_ENOSYS	No sys.
L4_EBADPROTO	Unsupported protocol.
L4_EADDRNOTAVAIL	Address not available.
L4_ERRNOMAX	Maximum error value.
L4_ENOREPLY	No reply.
L4_EMMSGTOOSHORT	Message too short.


L4_MSGTOOLONG	Message too long.
L4_MSGMISSARG	Message has invalid capability.
L4_MSGERRRANGE	Error code range error.
L4_EIPC_LO	Communication error-range low.
L4_EIPC_HI	Communication error-range high.

Definition at line 31 of file [err.h](#).

### 13.1.9 Object Invocation

API for [L4](#) object invocation.

Collaboration diagram for Object Invocation:



#### Topics

- [Message Items](#) . . . . . 225  
*Message-item-related functionality.*
- [Timeouts](#) . . . . . 232  
*All kinds of timeouts and time related functions.*
- [Error Handling](#) . . . . . 241  
*Error handling for [L4](#) object invocation.*
- [Realtime API](#) . . . . . 247

- [Message Tag](#) . . . . . 247  
*API related to the message tag data type.*
- [Virtual Registers \(UTCBs\)](#) . . . . . 260  
*L4 Virtual Registers (UTCB).*

## Files

- file [utcb.h](#)  
*UTCB definitions.*

## Macros

- `#define L4_SYSF_NONE`  
*Capability selector flags.*

## Functions

- [l4\\_msgtag\\_t l4\\_ipc\\_send](#) ([l4\\_cap\\_idx\\_t](#) dest, [l4\\_utcb\\_t](#) \*utcb, [l4\\_msgtag\\_t](#) tag, [l4\\_timeout\\_t](#) timeout) [L4\\_NOTHROW](#)  
*Send a message to an object (do **not** wait for a reply).*
- [l4\\_msgtag\\_t l4\\_ipc\\_wait](#) ([l4\\_utcb\\_t](#) \*utcb, [l4\\_umword\\_t](#) \*label, [l4\\_timeout\\_t](#) timeout) [L4\\_NOTHROW](#)  
*Wait for an incoming message from any possible sender.*
- [l4\\_msgtag\\_t l4\\_ipc\\_receive](#) ([l4\\_cap\\_idx\\_t](#) object, [l4\\_utcb\\_t](#) \*utcb, [l4\\_timeout\\_t](#) timeout) [L4\\_NOTHROW](#)  
*Wait for a message from a specific source.*
- [l4\\_msgtag\\_t l4\\_ipc\\_call](#) ([l4\\_cap\\_idx\\_t](#) object, [l4\\_utcb\\_t](#) \*utcb, [l4\\_msgtag\\_t](#) tag, [l4\\_timeout\\_t](#) timeout) [L4\\_NOTHROW](#)  
*Object call (usual invocation).*
- [l4\\_msgtag\\_t l4\\_ipc\\_reply\\_and\\_wait](#) ([l4\\_utcb\\_t](#) \*utcb, [l4\\_msgtag\\_t](#) tag, [l4\\_umword\\_t](#) \*label, [l4\\_timeout\\_t](#) timeout) [L4\\_NOTHROW](#)  
*Reply and wait operation (uses the reply capability).*
- [l4\\_msgtag\\_t l4\\_ipc\\_send\\_and\\_wait](#) ([l4\\_cap\\_idx\\_t](#) dest, [l4\\_utcb\\_t](#) \*utcb, [l4\\_msgtag\\_t](#) tag, [l4\\_umword\\_t](#) \*label, [l4\\_timeout\\_t](#) timeout) [L4\\_NOTHROW](#)  
*Send a message and do an open wait.*
- [l4\\_msgtag\\_t l4\\_ipc](#) ([l4\\_cap\\_idx\\_t](#) dest, [l4\\_utcb\\_t](#) \*utcb, [l4\\_umword\\_t](#) flags, [l4\\_umword\\_t](#) slabel, [l4\\_msgtag\\_t](#) tag, [l4\\_umword\\_t](#) \*rlabel, [l4\\_timeout\\_t](#) timeout) [L4\\_NOTHROW](#)  
*Generic L4 object invocation.*
- [l4\\_msgtag\\_t l4\\_ipc\\_sleep](#) ([l4\\_timeout\\_t](#) timeout) [L4\\_NOTHROW](#)  
*Sleep for an amount of time.*
- [l4\\_msgtag\\_t l4\\_ipc\\_sleep\\_ms](#) ([l4\\_uint32\\_t](#) ms) [L4\\_NOTHROW](#)  
*Sleep for a certain amount of milliseconds.*
- [l4\\_msgtag\\_t l4\\_ipc\\_sleep\\_us](#) ([l4\\_uint64\\_t](#) us) [L4\\_NOTHROW](#)  
*Sleep for a certain amount of microseconds.*
- `int l4_sndfpage_add` ([l4\\_fpage\\_t](#) const snd\_fpage, unsigned long snd\_base, [l4\\_msgtag\\_t](#) \*tag) [L4\\_NOTHROW](#)  
*Add a flexpage to be sent to the UTCB.*

### 13.1.9.1 Detailed Description

API for [L4](#) object invocation.

#### Include File

```
#include <l4/sys/ipc.h>
```

General abstractions for [L4](#) object invocation. The basic principle is that all objects are denoted by a capability that is accessed via a capability selector (see [Capabilities](#)).

This set of functions is common to all kinds of objects provided by the [L4](#) micro kernel. The concrete semantics of an invocation depends on the object that shall be invoked.

Objects may be invoked in various ways, the most common way is to use a *call* operation ([l4\\_ipc\\_call\(\)](#)). However, there are a lot more flavours available that have a semantics depending on the object.

#### See also

[IPC-Gate API](#)

[L4 Inter-Process Communication \(IPC\)](#)

### 13.1.9.2 Timeouts during IPC

IPC operation between two communication partners may consist of up to two phases (send phase and receive phase). For both phases, a timeout may be specified (send timeout and receive timeout).

#### Note

When IPC communication happens across CPU cores and a timeout is specified, then the counting of the timeout only begins after the target thread has been scheduled at least once. In particular, this means that an IPC timeout, including a timeout of zero, may be delayed depending on the scheduling on the target CPU core. If a higher priority thread on the target core is executing a busy loop, that delay may even be indefinitely.

#### See also

[Timeouts](#)

### 13.1.9.3 Macro Definition Documentation

#### 13.1.9.3.1 L4\_SYSF\_NONE

```
#define L4_SYSF_NONE
```

Capability selector flags.

These flags determine the concrete operation when a kernel object is invoked.

The following combinations of flags are supported when invoking IPC (see [l4\\_ipc\(\)](#)); with other combinations, behavior is undefined:

- [L4\\_SYSF\\_SEND](#): send to specified partner
- [L4\\_SYSF\\_RECV](#): receive from specified partner
- [L4\\_SYSF\\_RECV](#) | [L4\\_SYSF\\_OPEN\\_WAIT](#): receive from any sending partner; see [L4\\_SYSF\\_WAIT](#)
- [L4\\_SYSF\\_SEND](#) | [L4\\_SYSF\\_RECV](#): call specified partner; see [L4\\_SYSF\\_CALL](#)
- [L4\\_SYSF\\_SEND](#) | [L4\\_SYSF\\_RECV](#) | [L4\\_SYSF\\_OPEN\\_WAIT](#): send to specified partner and receive from any sending partner; see [L4\\_SYSF\\_SEND\\_AND\\_WAIT](#)
- [L4\\_SYSF\\_REPLY](#) | [L4\\_SYSF\\_SEND](#): reply to caller
- [L4\\_SYSF\\_REPLY](#) | [L4\\_SYSF\\_SEND](#) | [L4\\_SYSF\\_RECV](#): call the caller
- [L4\\_SYSF\\_REPLY](#) | [L4\\_SYSF\\_SEND](#) | [L4\\_SYSF\\_RECV](#) | [L4\\_SYSF\\_OPEN\\_WAIT](#): reply to caller and receive from any sending partner; see [L4\\_SYSF\\_REPLY\\_AND\\_WAIT](#) Empty set of flags.

Definition at line 55 of file [consts.h](#).

### 13.1.9.4 Function Documentation

#### 13.1.9.4.1 [l4\\_ipc\(\)](#)

```
l4_msgtag_t l4_ipc (
    l4_cap_idx_t dest,
    l4_utcb_t * utcb,
    l4_umword_t flags,
    l4_umword_t slabel,
    l4_msgtag_t tag,
    l4_umword_t * rlabel,
    l4_timeout_t timeout) [inline]
```

Generic [L4](#) object invocation.

#### Parameters

	<i>dest</i>	Destination object. <a href="#">L4_INVALID_CAP</a> denotes the current thread. An IPC to the current thread will always abort after the specified timeout and can be used for sleeping without busy waiting.
	<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. See <a href="#">l4_utcb</a> .
	<i>flags</i>	Invocation flags (see <a href="#">L4_SYSF_NONE</a> ).
	<i>slabel</i>	Send label if applicable (may be seen by the receiver).
	<i>tag</i>	Sending message tag.
out	<i>rlabel</i>	Receiving label.
	<i>timeout</i>	Timeout pair (see <a href="#">l4_timeout_t</a> ).

#### Returns

return tag





### 13.1.9.4.2 l4\_ipc\_call()

```
l4_msgtag_t l4_ipc_call (
    l4_cap_idx_t object,
    l4_utcb_t * utcb,
    l4_msgtag_t tag,
    l4_timeout_t timeout) [inline]
```

Object call (usual invocation).

#### Parameters

<i>object</i>	Capability selector for the object to call. A value of <a href="#">L4_INVALID_CAP</a> denotes the current thread and will abort the IPC after the time specified in the <code>snd</code> part of the <code>timeout</code> parameter has expired.
<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. See <a href="#">l4_utcb</a> .
<i>tag</i>	Message tag to describe the message to be sent.
<i>timeout</i>	Timeout pair for send an receive phase (see <a href="#">l4_timeout_t</a> ).

#### Returns

result tag

A message is sent to the object and the invoker waits for a reply from the object. Messages from other sources are not accepted.

#### Note

The send-to-receive transition needs no time, the object can reply with a send timeout of zero.

If a finite receive timeout is specified, the IPC receive operation could abort before the partner was able to send the reply message. Under certain circumstances the partner may still have the temporary reply capability to the calling thread and may use this capability to reply to the caller at a later, unexpected time specifying an arbitrary IPC label. This case is relevant for servers which call another, possibly untrusted, server while serving a client request.

#### See also

[L4 Inter-Process Communication \(IPC\)](#)

#### Examples

[examples/sys/aliens/main.c](#), [examples/sys/ipc/ipc\\_example.c](#), and [examples/sys/singlestep/main.c](#).

Definition at line 569 of file [ipc.h](#).


References [l4\\_ipc\(\)](#), [L4\\_NOTHROW](#), and [L4\\_SYSF\\_CALL](#).

Referenced by [\\_\\_l4\\_kdebug\\_3\\_text\(\)](#), [\\_\\_l4\\_kdebug\\_op\(\)](#), [\\_\\_l4\\_kdebug\\_op\\_1\(\)](#), [\\_\\_l4\\_kdebug\\_text\(\)](#), [L4::lpc::lostream::call\(\)](#), [fiasco\\_amd64\\_segment\\_info\(\)](#), [fiasco\\_amd64\\_set\\_fs\(\)](#), [fiasco\\_amd64\\_set\\_segment\\_base\(\)](#), [fiasco\\_gdt\\_get\\_entry\\_offset\(\)](#), [fiasco\\_gdt\\_set\(\)](#), [fiasco\\_ldt\\_set\(\)](#), [l4\\_icu\\_bind\\_u\(\)](#), [l4\\_icu\\_info\\_u\(\)](#), [l4\\_icu\\_msi\\_info\\_u\(\)](#), [l4\\_icu\\_set\\_mode\\_u\(\)](#), [l4\\_icu\\_unbind\\_u\(\)](#), [l4\\_irq\\_bind\\_vcpu\\_u\(\)](#), [l4\\_irq\\_detach\\_u\(\)](#), [l4\\_irq\\_receive\\_u\(\)](#), [l4\\_kd\\_enter\(\)](#), [l4\\_thread\\_ex\\_regs\\_u\(\)](#), [l4\\_thread\\_vcpu\\_control\\_ext\\_u\(\)](#), [l4\\_thread\\_vcpu\\_control\\_u\(\)](#), [l4\\_vcon\\_get\\_attr\\_u\(\)](#), [l4\\_vcon\\_set\\_attr\\_u\(\)](#), [l4util\\_ioport\\_map\(\)](#), and [L4::Thread::modify\\_senders\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 13.1.9.4.3 l4\_ipc\_receive()

```
l4_msgtag_t l4_ipc_receive (
    l4_cap_idx_t object,
    l4_utcb_t * utcb,
    l4_timeout_t timeout) [inline]
```

Wait for a message from a specific source.

### Parameters

<i>object</i>	Thread or IRQ object to receive a message from. A value of <a href="#">L4_INVALID_CAP</a> denotes the current thread. This can be used for sleeping without busy waiting for the time specified in the <code>rcv</code> part of the <code>timeout</code> parameter.
<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. See <a href="#">l4_utcb</a> .
<i>timeout</i>	Timeout pair (see <a href="#">l4_timeout_t</a> , only the receive part matters).

### Returns

result tag.

This operation waits for a message from the specified object. Messages from other sources are not accepted by this operation. The operation does not include a send phase, this means no message is sent to the object. See [l4\\_ipc\\_wait\(\)](#) for general message receiving.

### Note

This operation is used to receive messages from a specific IRQ or thread. Receiving from IPC gates or any other objects does not work. It is not common to use the receive-only IPC operation for normal client/server communication.

### See also

[L4 Inter-Process Communication \(IPC\)](#)

### Examples

[examples/sys/aliens/main.c](#), [examples/sys/singlestep/main.c](#), [examples/sys/start-with-exc/main.c](#), and [examples/sys/utcb-ipc/main.c](#).

Definition at line 606 of file [ipc.h](#).


References [l4\\_ipc\(\)](#), [L4\\_NOTHROW](#), [L4\\_SYSF\\_RECV](#), and [l4\\_msgtag\\_t::raw](#).

Referenced by [l4\\_ipc\\_sleep\(\)](#), and [l4\\_thread\\_yield\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



#### 13.1.9.4.4 l4\_ipc\_reply\_and\_wait()

```

l4_msgtag_t l4_ipc_reply_and_wait (
    l4_utcb_t * utcb,
    l4_msgtag_t tag,
    l4_umword_t * label,
    l4_timeout_t timeout) [inline]
  
```

Reply and wait operation (uses the *reply* capability).

##### Parameters

	<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. See <a href="#">l4_utcb</a> .
	<i>tag</i>	Describes the message to be sent as reply.
out	<i>label</i>	Label assigned to the source object of the received message.
	<i>timeout</i>	Timeout pair (see <a href="#">l4_timeout_t</a> ).

##### Returns

result tag

A message is sent to the previous caller using the implicit reply capability. Afterwards the invoking thread waits for a message from any source.

##### Note

This is the standard server operation: it sends a reply to the actual client and waits for the next incoming request, which may come from any other client.

In case of multiple senders trying to send to the thread performing this system call, the thread receives from a sender with the highest priority. In this respect, IRQ sources have the highest priority 255.

See also

[L4 Inter-Process Communication \(IPC\)](#)

Examples


[examples/sys/ipc/ipc\\_example.c](#).

Definition at line 576 of file [ipc.h](#).


References [L4\\_INVALID\\_CAP](#), [l4\\_ipc\(\)](#), [L4\\_NOTHROW](#), and [L4\\_SYSF\\_REPLY\\_AND\\_WAIT](#).

Referenced by [L4::ipc::loststream::reply\\_and\\_wait\(\)](#), and [L4::Server< LOOP\\_HOOKS >::reply\\_n\\_wait\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



#### 13.1.9.4.5 l4\_ipc\_send()

```

l4_msgtag_t l4_ipc_send (
    l4_cap_idx_t dest,
    l4_utcb_t * utcb,
    l4_msgtag_t tag,
    l4_timeout_t timeout) [inline]
  
```

Send a message to an object (do **not** wait for a reply).

**Parameters**

---

<i>dest</i>	Capability selector for the destination object. A value of <a href="#">L4_INVALID_CAP</a> denotes the current thread and could be used for sleeping without busy waiting for the time specified in the <code>snd</code> part of the <code>timeout</code> parameter.
<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. See <a href="#">l4_utcb</a> .
<i>tag</i>	Descriptor for the message to be sent.
<i>timeout</i>	Timeout pair (see <a href="#">l4_timeout_t</a> ) only send part is relevant.

### Returns

Syscall return tag for the send-only operation, this means there is no return value except [L4\\_MSGTAG\\_ERROR](#) indicating success or failure of the send operation. Use [l4\\_ipc\\_error\(\)](#) to check for errors and **do not** use [l4\\_error\(\)](#).

A message is sent to the destination object. There is no receive phase included. The invoker continues working after sending the message.

### Note

This is a special-purpose message transfer. Objects usually support only invocation via [l4\\_ipc\\_call\(\)](#) consisting of a send phase and a receive phase for returning the result of the object invocation. For example, [l4\\_icu\\_unmask\(\)](#), [l4\\_icu\\_mask\(\)](#) and [l4\\_irq\\_trigger\(\)](#) use send-only IPC operations for object invocation.

### See also

[L4 Inter-Process Communication \(IPC\)](#)

### Examples

[examples/sys/start-with-exc/main.c](#), and [examples/sys/utcb-ipc/main.c](#).

Definition at line 590 of file [ipc.h](#).

References [l4\\_ipc\(\)](#), [L4\\_NOTHROW](#), and [L4\\_SYSF\\_SEND](#).


Referenced by [l4\\_irq\\_trigger\\_u\(\)](#), [l4\\_irq\\_unmask\\_u\(\)](#), [l4\\_vcon\\_send\\_u\(\)](#), [L4::Server< LOOP\\_HOOKS >::reply\\_n\\_wait\(\)](#), and [L4::lpc::Ostream::send\(\)](#).

Here is the call graph for this function:





Here is the caller graph for this function:



#### 13.1.9.4.6 l4\_ipc\_send\_and\_wait()

```

l4_msgtag_t l4_ipc_send_and_wait (
    l4_cap_idx_t dest,
    l4_utcb_t * utcb,
    l4_msgtag_t tag,
    l4_umword_t * label,
    l4_timeout_t timeout) [inline]

```

Send a message and do an open wait.

#### Parameters

	<i>dest</i>	Object to send a message to. A value of <a href="#">L4_INVALID_CAP</a> denotes the current thread and will abort the IPC after the time specified in the <code>snd</code> part of the <code>timeout</code> parameter has expired.
	<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. See <a href="#">l4_utcb</a> .
	<i>tag</i>	Describes the message that shall be sent.
out	<i>label</i>	Label assigned to the source object of the receive phase.
	<i>timeout</i>	Timeout pair (see <a href="#">l4_timeout_t</a> ).

#### Returns

result tag

A message is sent to the destination object and the invoking thread waits for a reply from any source.

**Note**

This is a special-purpose operation and shall not be used in general applications.

In case of multiple senders trying to send to the thread performing this system call, the thread receives from a sender with the highest priority. In this respect, IRQ sources have the highest priority 255.

**See also**

[L4 Inter-Process Communication \(IPC\)](#)

Definition at line 583 of file [ipc.h](#).


References [l4\\_ipc\(\)](#), [L4\\_NOTHROW](#), and [L4\\_SYSF\\_SEND\\_AND\\_WAIT](#).

Referenced by [l4\\_irq\\_wait\\_u\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:

**13.1.9.4.7 l4\_ipc\_sleep()**

```
l4_msgtag_t l4_ipc_sleep (
    l4_timeout_t timeout) [inline]
```

Sleep for an amount of time.

**Parameters**

<i>timeout</i>	Timeout pair (see <a href="#">l4_timeout_t</a> , the receive part matters).
----------------	---

### Returns

error code:

- [L4\\_IPC\\_RETIMEOUT](#): success
- [L4\\_IPC\\_RECANCELED](#) woken up by a different thread ([l4\\_thread\\_ex\\_regs\(\)](#)).

The invoking thread waits until the timeout is expired or the wait was aborted by another thread by [l4\\_thread\\_ex\\_regs\(\)](#).

### See also


[L4 Inter-Process Communication \(IPC\)](#)

Definition at line 615 of file [ipc.h](#).


References [L4\\_INVALID\\_CAP](#), [l4\\_ipc\\_receive\(\)](#), and [L4\\_NOTHROW](#).

Referenced by [l4\\_ipc\\_sleep\\_ms\(\)](#), [l4\\_ipc\\_sleep\\_us\(\)](#), and [l4\\_sleep\\_forever\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



#### 13.1.9.4.8 l4\_ipc\_sleep\_ms()

```
l4_msgtag_t l4_ipc_sleep_ms (
    l4_uint32_t ms) [inline]
```

Sleep for a certain amount of milliseconds.

##### Parameters

<i>ms</i>	Number of milliseconds to wait.
-----------	---------------------------------

##### Returns

error code:

- [L4\\_IPC\\_RETIMEOUT](#): success
- [L4\\_IPC\\_RECANCELED](#) woken up by a different thread ([l4\\_thread\\_ex\\_regs\(\)](#)).

The invoking thread waits until the timeout is expired or the wait was aborted by another thread by [l4\\_thread\\_ex\\_regs\(\)](#).


##### See also

[L4 Inter-Process Communication \(IPC\)](#)

Definition at line 619 of file [ipc.h](#).

References [l4\\_ipc\\_sleep\(\)](#), [L4\\_IPC\\_TIMEOUT\\_NEVER](#), [L4\\_NOTHROW](#), and [l4\\_timeout\(\)](#).

Here is the call graph for this function:



#### 13.1.9.4.9 l4\_ipc\_sleep\_us()

```
l4_msgtag_t l4_ipc_sleep_us (
    l4_uint64_t us) [inline]
```

Sleep for a certain amount of microseconds.

##### Parameters

---

<i>us</i>	Number of microseconds to wait.
-----------	---------------------------------

#### Returns

error code:

- [L4\\_IPC\\_RETIMEOUT](#): success
- [L4\\_IPC\\_RECANCELED](#) woken up by a different thread ([l4\\_thread\\_ex\\_regs\(\)](#)).

The invoking thread waits until the timeout is expired or the wait was aborted by another thread by [l4\\_thread\\_ex\\_regs\(\)](#).


#### See also

[L4 Inter-Process Communication \(IPC\)](#)

Definition at line 626 of file [ipc.h](#).

References [l4\\_ipc\\_sleep\(\)](#), [L4\\_IPC\\_TIMEOUT\\_NEVER](#), [L4\\_NOTHROW](#), and [l4\\_timeout\(\)](#).

Here is the call graph for this function:



#### 13.1.9.4.10 l4\_ipc\_wait()

```

l4_msgtag_t l4_ipc_wait (
    l4_utcb_t * utcb,
    l4_umword_t * label,
    l4_timeout_t timeout) [inline]
  
```

Wait for an incoming message from any possible sender.

#### Parameters

	<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. See <a href="#">l4_utcb</a> .
out	<i>label</i>	Label assigned to the source object (IPC gate or IRQ).
	<i>timeout</i>	Timeout pair (see <a href="#">l4_timeout_t</a> , only the receive part is used).

**Returns**

return tag

This operation does an open wait, and therefore needs no capability to denote the possible source of a message. This means the calling thread waits for an incoming message from any possible source. There is no send phase included in this operation.

The usual usage of this function is to call that function when entering a server loop in a user-level server that implements user-level objects, see also [l4\\_ipc\\_reply\\_and\\_wait\(\)](#).

**Note**

In case of multiple senders trying to send to the thread performing this system call, the thread receives from a sender with the highest priority. In this respect, IRQ sources have the highest priority 255.

**See also**

[L4 Inter-Process Communication \(IPC\)](#)

**Examples**

[examples/sys/ipc/ipc\\_example.c](#).

Definition at line 597 of file [ipc.h](#).


References [L4\\_INVALID\\_CAP](#), [l4\\_ipc\(\)](#), [L4\\_NOTHROW](#), [L4\\_SYSF\\_WAIT](#), and [l4\\_msgtag\\_t::raw](#).

Referenced by [L4::Server< LOOP\\_HOOKS >::reply\\_n\\_wait\(\)](#), and [L4::lpc::lstream::wait\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



#### 13.1.9.4.11 l4\_sndfpage\_add()

```
int l4_sndfpage_add (
    l4_fpage_t const snd_fpage,
    unsigned long snd_base,
    l4_msgtag_t * tag) [inline]
```

Add a flexpage to be sent to the UTCB.

##### Parameters

	<i>snd_fpage</i>	Flexpage.
	<i>snd_base</i>	Send base.
in, out	<i>tag</i>	Tag to be updated. Only the number of items is incremented in the updated tag, all other members remain unmodified.

##### Returns

0 on success, negative error code otherwise


##### See also

[L4 Inter-Process Communication \(IPC\)](#)

Definition at line 689 of file [ipc.h](#).

References [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).


Here is the call graph for this function:



#### 13.1.9.5 Message Items

Message-item-related functionality.

Collaboration diagram for Message Items:



## Topics

- Attributes and additional permissions for object send items . . . . . 231  
*These rights need to be added to the `snd_base` when mapping and control internal behavior.*

## Data Structures

- struct `l4_snd_fpage_t`  
*Send-flexpage types.*

## Enumerations

- enum `l4_fpage_cacheability_opt_t` { `L4_FPAGE_CACHE_OPT` = 0x1 , `L4_FPAGE_CACHEABLE` = 0x3 , `L4_FPAGE_BUFFERABLE` = 0x5 , `L4_FPAGE_UNCACHEABLE` = 0x1 }
  - enum `l4_msg_item_consts_t` {  
`L4_ITEM_MAP` = 8 , `L4_ITEM_CONT` = 1 , `L4_MAP_ITEM_GRANT` = 2 , `L4_MAP_ITEM_MAP` = 0 ,  
`L4_RCV_ITEM_FORWARD_MAPPINGS` = 1 , `L4_RCV_ITEM_SINGLE_CAP` = `L4_ITEM_MAP` | 2 ,  
`L4_RCV_ITEM_LOCAL_ID` = 4 }
- Cacheability options for memory send items.*
- Constants for message items.*

## Functions

- `l4_umword_t l4_map_control` (`l4_umword_t` spot, unsigned char cache, unsigned grant) `L4_NOTHROW`  
*Create the first word for a map item that is a send item for the memory space.*
- `l4_umword_t l4_map_obj_control` (`l4_umword_t` spot, unsigned grant) `L4_NOTHROW`  
*Create the first word for a map item that is a send item for the object space.*

### 13.1.9.5.1 Detailed Description

Message-item-related functionality.

Message items are typed items that are used for transferring capabilities during IPC. There are three sub-types of typed message items with variations in the layout:

1. Typed message items set by the sender in its message registers (MRs) of the UTCB for specifying what shall be sent.
2. Typed message items set by the receiver in its buffer registers (BRs) of the UTCB for specifying which types of capabilities may be received at which addresses.
3. Typed message items set by the kernel in the receiver's message registers (MRs) of the UTCB for providing information about the transfer to the receiver.

They are abbreviated by *send item*, *receive item*, and *return item*, respectively.

A typed message item in the message registers (case 1 and case 3) always consists of two words (even if it is a void item). The size of a typed message item in the buffer registers (case 2) is determined by its first word. The size is up to three words (see `L4_RCV_ITEM_SINGLE_CAP` and `L4_RCV_ITEM_FORWARD_MAPPINGS`). A void item in the buffer registers consists of a single word.

## Include File

```
#include <l4/sys/types.h>
```



### 13.1.9.5.2 Enumeration Type Documentation

#### 13.1.9.5.2.1 l4\_fpage\_cacheability\_opt\_t

```
enum l4_fpage_cacheability_opt_t
```

Cacheability options for memory send items.

Only the IPC sender and the thread performing the map operation can specify the caching mode of the target mapping. By default, the caching mode of the sender is used as caching mode for the target mapping. If `L4_FPAGE_CACHE_OPT` is set in the send item, the caching mode is overridden by the respective mode from below.

#### Enumerator

<code>L4_FPAGE_CACHE_OPT</code>	Enable the cacheability option in a memory send item. Without this flag, the options are copied from the sender.
<code>L4_FPAGE_CACHEABLE</code>	Cacheability option to enable caches for the mapping. Implies <a href="#">L4_FPAGE_CACHE_OPT</a> .
<code>L4_FPAGE_BUFFERABLE</code>	Cacheability option to enable buffered writes for the mapping. Implies <a href="#">L4_FPAGE_CACHE_OPT</a> .
<code>L4_FPAGE_UNCACHEABLE</code>	Cacheability option to disable caching for the mapping. Implies <a href="#">L4_FPAGE_CACHE_OPT</a> .

Definition at line 303 of file [\\_\\_l4\\_fpage.h](#).

#### 13.1.9.5.2.2 l4\_msg\_item\_consts\_t

```
enum l4_msg_item_consts_t
```

Constants for message items.

#### Enumerator

<code>L4_ITEM_MAP</code>	Identify a message item as <i>map item</i> .
<code>L4_ITEM_CONT</code>	Denote that the following item shall be put into the same receive item as this one.

L4_MAP_ITEM_GRANT	<p>Flag as <i>grant</i> instead of <i>map</i> operation. This means, the sender delegates access to the receiver and the kernel removes the rights from the sender (basically a move operation). The mapping in the receiver gets the new parent of any child mappings of the mapping of the sender. Rights revocation via send item/flexpage is <i>not</i> guaranteed to be applied to descendant mappings in case of grant. See <a href="#">Spaces and Mappings</a> for more details on map/grant.</p> <p><b>Note</b></p> <p>The grant operation is not performed if the resulting rights of the receiver mapping would not contain the <a href="#">L4_CAP_FPAGE_R</a> bit (for object capabilities) or none of the <a href="#">L4_FPAGE_RWX</a> bits (memory and IO ports). In that case, the mapping is not created in the receiver space and not removed from the sender space.</p> <p>If the removal of the whole mapping from the sender is not possible because the size of the mapped frame at the sender exceeds the size defined by the send or receive flexpage, the grant operation is turned into a regular map operation and the mapping is <i>not</i> removed from the sender. This would happen if, for example, a smaller part of an <a href="#">L4</a> superpage mapping shall be granted.</p>
L4_MAP_ITEM_MAP	Flag as usual <i>map</i> operation.
L4_RCV_ITEM_FORWARD_MAPPINGS	<p>This flag specifies if received capabilities shall be mapped to a particular task instead of the invoking task. This flag may be used only if <a href="#">L4_RCV_ITEM_LOCAL_ID</a> is unset.</p> <p>Setting this flag increases the size of the buffer item by one word. This word is used to specify a capability index for the task that shall receive the mappings.</p>
L4_RCV_ITEM_SINGLE_CAP	<p>Mark the receive buffer to be a small receive item that describes a buffer for a single object capability. A receive item needs to specify a <i>receive window</i>. The receive window determines which kind of capabilities (object, memory, I/O ports) may be received where in the respective space. If this flag is unset, the receive window is specified in the second word of the receive item via a <a href="#">flexpage</a>. If this flag is set, the receive window consists of a single capability index in the object space and the capability index is specified in the most significant bits of the first word of the receive item (see <a href="#">L4_CAP_SHIFT</a>).</p>

L4_RCV_ITEM_LOCAL_ID	<p>The receiver requests to receive a local ID instead of a mapping whenever possible. This flag may be used only if <a href="#">L4_RCV_ITEM_SINGLE_CAP</a> is set and <a href="#">L4_RCV_ITEM_FORWARD_MAPPINGS</a> is unset.</p> <p>When this flag is set, then,</p> <ul style="list-style-type: none"> <li>• when sender and receiver are bound to the same task, then no mapping is done for this item and just the raw flexpage (<a href="#">l4_fpage_t</a>) is transferred,</li> <li>• otherwise, when the sender specified an IPC gate for transfer that is bound to a thread that is bound to the same task as the receiving thread, then no mapping is done for this item and just the bitwise OR ( ) of the label and the <a href="#">L4_CAP_FPAGE_W</a> and <a href="#">L4_CAP_FPAGE_S</a> permissions that would have been mapped is transferred,</li> <li>• otherwise a regular mapping is done for this item.</li> </ul>
----------------------	---

Definition at line 210 of file [consts.h](#).

### 13.1.9.5.3 Function Documentation

#### 13.1.9.5.3.1 l4\_map\_control()

```
l4_umword_t l4_map_control (
    l4_umword_t spot,
    unsigned char cache,
    unsigned grant) [inline]
```

Create the first word for a map item that is a send item for the memory space.

#### Parameters

<i>spot</i>	Hot spot address, used to determine what is actually mapped when send and receive flexpage have differing sizes.
<i>cache</i>	Cacheability hints for memory flexpages. See <a href="#">Cacheability options</a> .
<i>grant</i>	Indicates if it is a map or a grant item. Allowed values: <a href="#">L4_MAP_ITEM_MAP</a> , <a href="#">L4_MAP_ITEM_GRANT</a> .

#### Returns


The value to be used as first word in a send item for memory.

Definition at line 754 of file [\\_\\_l4\\_fpage.h](#).

References [L4\\_FPAGE\\_CONTROL\\_MASK](#), [L4\\_ITEM\\_MAP](#), and [L4\\_NOTHROW](#).

Referenced by [l4\\_map\\_obj\\_control\(\)](#).

Here is the caller graph for this function:



### 13.1.9.5.3.2 l4\_map\_obj\_control()

```
l4_umword_t l4_map_obj_control (
    l4_umword_t spot,
    unsigned grant) [inline]
```

Create the first word for a map item that is a send item for the object space.

#### Parameters

<i>spot</i>	Hot spot address, used to determine what is actually mapped when send and receive flexpages have different size.
<i>grant</i>	Indicates if it is a map item or a grant item. Allowed values: <a href="#">L4_MAP_ITEM_MAP</a> , <a href="#">L4_MAP_ITEM_GRANT</a> .

#### Returns

The value to be used as first word in a send item for kernel objects or IO-ports.

Definition at line 761 of file [\\_\\_l4\\_fpage.h](#).


References [l4\\_map\\_control\(\)](#), and [L4\\_NOTHROW](#).

Referenced by [l4\\_icu\\_bind\\_u\(\)](#), [l4\\_icu\\_unbind\\_u\(\)](#), [l4\\_irq\\_bind\\_vcpu\\_u\(\)](#), and [L4::Cap\\_base::snd\\_base\(\)](#).

Here is the call graph for this function:




Here is the caller graph for this function:



#### 13.1.9.5.4 Attributes and additional permissions for object send items

These rights need to be added to the `snd_base` when mapping and control internal behavior.

Collaboration diagram for Attributes and additional permissions for object send items:



#### Macros

- `#define L4_FPAGE_C_REF_CNT 0x00`  
*Mapping is reference-counted (default).*
- `#define L4_FPAGE_C_NO_REF_CNT 0x10`  
*Don't increase the reference counter.*
- `#define L4_FPAGE_C_OBJ_RIGHT1 0x20`  
*Object-type specific right.*
- `#define L4_FPAGE_C_OBJ_RIGHT2 0x40`  
*Object-type specific right.*
- `#define L4_FPAGE_C_OBJ_RIGHT3 0x80`  
*Object-type specific right.*
- `#define L4_FPAGE_C_OBJ_RIGHTS 0xe0`  
*All Object-type specific right bits.*
- `#define L4_FPAGE_C_IPCGATE_SVR L4_FPAGE_C_OBJ_RIGHT1`  
*The receiver may invoke IPC-gate-specific functions on the capability, for example, bind a thread to the gate and modify the label.*

#### 13.1.9.5.4.1 Detailed Description

These rights need to be added to the `snd_base` when mapping and control internal behavior.

The exact meaning depends on the type of capability (currently used only with IPC gates).

#### 13.1.9.5.4.2 Macro Definition Documentation

##### L4\_FPAGE\_C\_IPCGATE\_SVR

```
#define L4_FPAGE_C_IPCGATE_SVR L4_FPAGE_C_OBJ_RIGHT1
```

The receiver may invoke IPC-gate-specific functions on the capability, for example, bind a thread to the gate and modify the label.


Needed if the receiver implements the server side of an IPC gate.

Definition at line 288 of file `__l4_fpage.h`.

#### 13.1.9.6 Timeouts

All kinds of timeouts and time related functions.

Collaboration diagram for Timeouts:



#### Data Structures

- struct `l4_timeout_s`  
*Basic timeout specification.*
- union `l4_timeout_t`  
*Timeout pair.*

## Macros

- `#define L4_IPC_TIMEOUT_0 ((l4_timeout_s){0x0400})`  
*Timeout constants.*
- `#define L4_IPC_TIMEOUT_NEVER ((l4_timeout_s){0})`  
*never timeout*
- `#define L4_IPC_NEVER_INITIALIZER {0}`  
*never timeout, initializer*
- `#define L4_IPC_NEVER ((l4_timeout_t){0})`  
*never timeout*
- `#define L4_IPC_RECV_TIMEOUT_0 ((l4_timeout_t){0x00000400})`  
*0 receive timeout*
- `#define L4_IPC_SEND_TIMEOUT_0 ((l4_timeout_t){0x04000000})`  
*0 send timeout*
- `#define L4_IPC_BOTH_TIMEOUT_0 ((l4_timeout_t){0x04000400})`  
*0 receive and send timeout*
- `#define L4_TIMEOUT_US_NEVER (~0ULL)`  
*The waiting period in microseconds which is interpreted as "never" by l4\_timeout\_from\_us().*
- `#define L4_TIMEOUT_US_MAX ((1ULL << 41) - 1)`  
*The longest waiting period in microseconds accepted by l4\_timeout\_from\_us().*

## Typedefs

- `typedef struct l4_timeout_s l4_timeout_s`  
*Basic timeout specification.*
- `typedef union l4_timeout_t l4_timeout_t`  
*Timeout pair.*

## Functions

- `L4_CONSTEXPR l4_timeout_s l4_timeout_rel (unsigned man, unsigned exp) L4_NOTHROW`  
*Get relative timeout consisting of mantissa and exponent.*
- `L4_CONSTEXPR l4_timeout_t l4_ipc_timeout (unsigned snd_man, unsigned snd_exp, unsigned rcv_man, unsigned rcv_exp) L4_NOTHROW`  
*Convert explicit timeout values to l4\_timeout\_t type.*
- `L4_CONSTEXPR l4_timeout_t l4_timeout (l4_timeout_s snd, l4_timeout_s rcv) L4_NOTHROW`  
*Combine send and receive timeout in a timeout.*
- `L4_CONSTEXPR void l4_snd_timeout (l4_timeout_s snd, l4_timeout_t *to) L4_NOTHROW`  
*Set send timeout in given to timeout.*
- `L4_CONSTEXPR void l4_rcv_timeout (l4_timeout_s rcv, l4_timeout_t *to) L4_NOTHROW`  
*Set receive timeout in given to timeout.*
- `L4_CONSTEXPR l4_kernel_clock_t l4_timeout_rel_get (l4_timeout_s to) L4_NOTHROW`  
*Get clock value of out timeout.*
- `L4_CONSTEXPR unsigned l4_timeout_is_absolute (l4_timeout_s to) L4_NOTHROW`  
*Return whether the given timeout is absolute or not.*
- `L4_CONSTEXPR l4_kernel_clock_t l4_timeout_get (l4_kernel_clock_t cur, l4_timeout_s to) L4_NOTHROW`  
*Get clock value for a clock + a timeout.*
- `l4_timeout_s l4_timeout_abs (l4_kernel_clock_t pint, int br) L4_NOTHROW`  
*Set an absolute timeout.*
- `unsigned l4_utcb_mr64_idx (unsigned idx) L4_NOTHROW`  
*Get index into 64bit message registers alias from native-sized index.*

### 13.1.9.6.1 Detailed Description

All kinds of timeouts and time related functions.

### 13.1.9.6.2 Macro Definition Documentation

#### 13.1.9.6.2.1 L4\_IPC\_TIMEOUT\_0

```
#define L4_IPC_TIMEOUT_0 ((l4_timeout_s){0x0400})
```

Timeout constants.

0 timeout

Definition at line 73 of file [\\_\\_timeout.h](#).

Referenced by [L4::ipc\\_svr::Timeout\\_queue\\_hooks<HOOKS, BR\\_MAN>::timeout\(\)](#).

#### 13.1.9.6.2.2 L4\_TIMEOUT\_US\_MAX

```
#define L4_TIMEOUT_US_MAX ((1ULL << 41) - 1)
```

The longest waiting period in microseconds accepted by [l4\\_timeout\\_from\\_us\(\)](#).

See [l4\\_timeout\\_from\\_us\(\)](#) for an explanation.

Definition at line 91 of file [\\_\\_timeout.h](#).

### 13.1.9.6.3 Typedef Documentation

#### 13.1.9.6.3.1 l4\_timeout\_s

```
typedef struct l4_timeout_s l4_timeout_s
```

Basic timeout specification.

If bit 15 == 0, basically a floating point number with 10 bits mantissa and 5 bits exponent ( $t = m \cdot 2^e$ ).

If the mantissa is zero, the exponent encodes special values, see [L4\\_IPC\\_TIMEOUT\\_0](#) and [L4\\_IPC\\_TIMEOUT\\_NEVER](#).

If bit 15 == 1 the timeout is absolute and the lower 6 bits encode the index of the UTCB buffer register(s) holding the absolute 64-bit timeout value. On 32-bit systems, two consecutive UTCB buffer registers are used.

#### 13.1.9.6.3.2 l4\_timeout\_t

```
typedef union l4_timeout_t l4_timeout_t
```

Timeout pair.

For IPC there are usually a send and a receive timeout. So this structure contains a pair of timeouts.



#### 13.1.9.6.4 Function Documentation

##### 13.1.9.6.4.1 l4\_ipc\_timeout()

```
L4_CONSTEXPR l4_timeout_t l4_ipc_timeout (
    unsigned snd_man,
    unsigned snd_exp,
    unsigned rcv_man,
    unsigned rcv_exp) [inline]
```

Convert explicit timeout values to [l4\\_timeout\\_t](#) type.

##### Parameters

<i>snd_man</i>	Mantissa of send timeout.
<i>snd_exp</i>	Exponent of send timeout.
<i>rcv_man</i>	Mantissa of receive timeout.
<i>rcv_exp</i>	Exponent of receive timeout.

Definition at line 207 of file [\\_\\_timeout.h](#).

References [L4\\_NOTHROW](#), and [l4\\_timeout\(\)](#).

Here is the call graph for this function:



##### 13.1.9.6.4.2 l4\_rcv\_timeout()

```
L4_CONSTEXPR void l4_rcv_timeout (
    l4_timeout_s rcv,
    l4_timeout_t * to) [inline]
```

Set receive timeout in given to timeout.

##### Parameters

	<i>rcv</i>	Receive timeout
<i>out</i>	<i>to</i>	<a href="#">L4 timeout</a>

Definition at line 231 of file [\\_\\_timeout.h](#).

References [L4\\_NOTHROW](#).

#### 13.1.9.6.4.3 l4\_snd\_timeout()

```
L4_CONSTEXPR void l4_snd_timeout (
    l4_timeout_s snd,
    l4_timeout_t * to) [inline]
```

Set send timeout in given to timeout.

##### Parameters

	<i>snd</i>	Send timeout
out	<i>to</i>	L4 timeout

Definition at line 224 of file [\\_\\_timeout.h](#).

References [L4\\_NOTHROW](#).

#### 13.1.9.6.4.4 l4\_timeout()

```
L4_CONSTEXPR l4_timeout_t l4_timeout (
    l4_timeout_s snd,
    l4_timeout_s rcv) [inline]
```

Combine send and receive timeout in a timeout.

##### Parameters

<i>snd</i>	Send timeout
<i>rcv</i>	Receive timeout

##### Returns


L4 timeout

Definition at line 217 of file [\\_\\_timeout.h](#).

References [L4\\_NOTHROW](#).

Referenced by [l4\\_ipc\\_sleep\\_ms\(\)](#), [l4\\_ipc\\_sleep\\_us\(\)](#), [l4\\_ipc\\_timeout\(\)](#), and [L4::lpc\\_svr::Timeout\\_queue\\_hooks< HOOKS, BR\\_MAN](#)

Here is the caller graph for this function:



#### 13.1.9.6.4.5 l4\_timeout\_abs()

```
l4_timeout_s l4_timeout_abs (
    l4_kernel_clock_t pint,
    int br) [inline]
```

Set an absolute timeout.

##### Parameters

<i>pint</i>	Point in time in clocks
<i>br</i>	The buffer register the timeout shall be placed in. (

##### Note

On 32bit architectures the timeout needs two consecutive buffers.)

The absolute timeout value will be placed into the buffer register *br* of the current thread.

##### Returns


timeout value

Definition at line 392 of file [utcb.h](#).


References [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Referenced by [L4::lpc\\_svr::Timeout\\_queue\\_hooks< HOOKS, BR\\_MAN >::timeout\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



#### 13.1.9.6.4.6 l4\_timeout\_get()

```
L4_CONSTEXPR l4_kernel_clock_t l4_timeout_get (  
    l4_kernel_clock_t cur,  
    l4_timeout_s to) [inline]
```

Get clock value for a clock + a timeout.

##### Parameters

<i>cur</i>	Clock value
<i>to</i>	L4 timeout


##### Returns

Clock sum

Definition at line 261 of file [\\_\\_timeout.h](#).

References [L4\\_NOTHROW](#), [l4\\_timeout\\_is\\_absolute\(\)](#), and [l4\\_timeout\\_rel\\_get\(\)](#).

Here is the call graph for this function:



#### 13.1.9.6.4.7 l4\_timeout\_is\_absolute()

```
L4_CONSTEXPR unsigned l4_timeout_is_absolute (  
    l4_timeout_s to) [inline]
```

Return whether the given timeout is absolute or not.

##### Parameters

<i>to</i>	L4 timeout
-----------	------------

**Returns**

!= 0 if absolute, 0 if relative

Definition at line 254 of file [\\_\\_timeout.h](#).

References [L4\\_NOTHROW](#).

Referenced by [l4\\_timeout\\_get\(\)](#).

Here is the caller graph for this function:

**13.1.9.6.4.8 l4\_timeout\_rel()**

```
L4_CONSTEXPR l4_timeout_s l4_timeout_rel (  
    unsigned man,  
    unsigned exp) [inline]
```

Get relative timeout consisting of mantissa and exponent.

**Parameters**

<i>man</i>	Mantissa of timeout
<i>exp</i>	Exponent of timeout

**Returns**

timeout value

Definition at line 238 of file [\\_\\_timeout.h](#).

References [L4\\_NOTHROW](#).

#### 13.1.9.6.4.9 l4\_timeout\_rel\_get()

```
L4_CONSTEXPR l4_kernel_clock_t l4_timeout_rel_get (
    l4_timeout_s to) [inline]
```

Get clock value of out timeout.

##### Parameters

<i>to</i>	L4 timeout
-----------	------------

##### Returns


Clock value

Definition at line 245 of file [\\_\\_timeout.h](#).

References [L4\\_NOTHROW](#).

Referenced by [l4\\_timeout\\_get\(\)](#).

Here is the caller graph for this function:



#### 13.1.9.6.4.10 l4\_utcb\_mr64\_idx()

```
unsigned l4_utcb_mr64_idx (
    unsigned idx) [inline]
```

Get index into 64bit message registers alias from native-sized index.

##### Parameters

<i>idx</i>	Index to native-sized message register
------------	--

**Returns**


Index to 64bit message register alias

Definition at line 395 of file [utcb.h](#).

References [L4\\_INLINE](#), and [L4\\_NOTHROW](#).


Referenced by [l4\\_icu\\_msi\\_info\\_u\(\)](#).

Here is the caller graph for this function:

**13.1.9.7 Error Handling**

Error handling for [L4](#) object invocation.

Collaboration diagram for Error Handling:

**Enumerations**

- enum [l4\\_ipc\\_tcr\\_error\\_t](#) {  
[L4\\_IPC\\_ERROR\\_MASK](#) = 0x1F , [L4\\_IPC\\_SND\\_ERR\\_MASK](#) = 0x01 , [L4\\_IPC\\_ENOT\\_EXISTENT](#) = 0x04 ,  
[L4\\_IPC\\_RETIMEOUT](#) = 0x03 ,  
[L4\\_IPC\\_SETIMEOUT](#) = 0x02 , [L4\\_IPC\\_RECANCELED](#) = 0x07 , [L4\\_IPC\\_SECANCELED](#) = 0x06 ,  
[L4\\_IPC\\_REMAPFAILED](#) = 0x11 ,  
[L4\\_IPC\\_SEMAPFAILED](#) = 0x10 , [L4\\_IPC\\_RESNDPFTO](#) = 0x0b , [L4\\_IPC\\_SESNDPFTO](#) = 0x0a ,  
[L4\\_IPC\\_RERCVPFTO](#) = 0x0d ,  
[L4\\_IPC\\_SERCVPFTO](#) = 0x0c , [L4\\_IPC\\_REABORTED](#) = 0x0f , [L4\\_IPC\\_SEABORTED](#) = 0x0e ,  
[L4\\_IPC\\_REMSGCUT](#) = 0x09 ,  
[L4\\_IPC\\_SEMSGCUT](#) = 0x08 }

*Error codes in the error TCR.*

## Functions

- [l4\\_umword\\_t l4\\_ipc\\_error](#) ([l4\\_msgtag\\_t](#) tag, [l4\\_utcb\\_t](#) \*utcb) [L4\\_NOTHROW](#)  
*Get the IPC error code for an IPC operation.*
- [l4\\_ret\\_t l4\\_error](#) ([l4\\_msgtag\\_t](#) tag) [L4\\_NOTHROW](#)  
*Get IPC error code if any or message tag label otherwise for an IPC call.*
- [int l4\\_ipc\\_is\\_snd\\_error](#) ([l4\\_utcb\\_t](#) \*utcb) [L4\\_NOTHROW](#)  
*Returns whether an error occurred in send phase of an invocation.*
- [int l4\\_ipc\\_is\\_rcv\\_error](#) ([l4\\_utcb\\_t](#) \*utcb) [L4\\_NOTHROW](#)  
*Returns whether an error occurred in receive phase of an invocation.*
- [int l4\\_ipc\\_error\\_code](#) ([l4\\_utcb\\_t](#) \*utcb) [L4\\_NOTHROW](#)  
*Get the error condition of the last invocation from the TCR.*

### 13.1.9.7.1 Detailed Description

Error handling for [L4](#) object invocation.

#### Include File

```
#include <l4/sys/ipc.h>
```

### 13.1.9.7.2 Enumeration Type Documentation

#### 13.1.9.7.2.1 l4\_ipc\_tcr\_error\_t

```
enum l4_ipc_tcr_error_t
```

Error codes in the *error* TCR.

The error codes are accessible via the *error* TCR, see [l4\\_thread\\_regs\\_t.error](#).

#### Enumerator

<a href="#">L4_IPC_ERROR_MASK</a>	Mask for error bits.
<a href="#">L4_IPC_SND_ERR_MASK</a>	Send error mask.
<a href="#">L4_IPC_ENOT_EXISTENT</a>	Non-existing destination or source.
<a href="#">L4_IPC_RETIMEOUT</a>	Timeout during receive operation.
<a href="#">L4_IPC_SETIMEOUT</a>	Timeout during send operation.
<a href="#">L4_IPC_RECANCELED</a>	Receive operation canceled.
<a href="#">L4_IPC_SECANCELED</a>	Send operation canceled.
<a href="#">L4_IPC_REMAPFAILED</a>	Map flexpage failed in receive operation.
<a href="#">L4_IPC_SEMAPFAILED</a>	Map flexpage failed in send operation.
<a href="#">L4_IPC_RESNDPFTO</a>	Send-pagefault timeout in receive operation.
<a href="#">L4_IPC_SESNDPFTO</a>	Send-pagefault timeout in send operation.
<a href="#">L4_IPC_RERCVPFTO</a>	Receive-pagefault timeout in receive operation.



L4_IPC_SERCVPFTO	Receive-pagefault timeout in send operation.
L4_IPC_REABORTED	Receive operation aborted.
L4_IPC_SEABORTED	Send operation aborted.
L4_IPC_REMSGCUT	Received message truncated. Usually returned when the typed items to be sent by the IPC partner exceed the buffer registers of the respective types.
L4_IPC_SEMSGCUT	Sent message truncated. Usually returned when the typed items to be sent exceed the IPC partner's buffer registers of the respective types.

Definition at line 81 of file [ipc.h](#).

### 13.1.9.7.3 Function Documentation

#### 13.1.9.7.3.1 l4\_error()

```
l4_ret_t l4_error (
    l4_msgtag_t tag) [inline]
```

Get IPC error code if any or message tag label otherwise for an IPC call.

This function shall only be used if the IPC operation includes a receive phase (usually a call operation), otherwise no tag label is received and the return value of this function is undefined.

#### Parameters

<i>tag</i>	Message tag returned by the IPC call.
------------	---------------------------------------

#### Returns

In case of an IPC error, a negative error code in the range of [L4\\_EIPC\\_LO](#) to [L4\\_EIPC\\_HI](#) (see [l4\\_ipc\\_to\\_errno\(\)](#) and [l4\\_ipc\\_tcr\\_error\\_t](#)), otherwise the tag label. By convention, the callee can signal errors via a negative tag label (negated value from [l4\\_error\\_code\\_t](#)) and success via a non-negative value.

#### Examples

[examples/libs/l4re/streammap/client.cc](#), [examples/sys/aliens/main.c](#), [examples/sys/isr/main.c](#), [examples/sys/migrate/thread\\_migration.c](#), [examples/sys/singlestep/main.c](#), [examples/sys/start-with-exc/main.c](#), and [examples/sys/utcb-ipc/main.c](#).

Definition at line 650 of file [ipc.h](#).


References [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Referenced by [L4Re::Mem\\_alloc::alloc\(\)](#), [L4virtio::Driver::Device::bind\\_notification\\_irq\(\)](#), [L4virtio::Driver::Virtio\\_net\\_device::bind\\_rx\\_net\\_device\(\)](#), [L4::cap\\_dynamic\\_cast\(\)](#), [L4virtio::Driver::Device::driver\\_connect\(\)](#), [fiasco\\_dump\\_kmem\\_stats\(\)](#), [fiasco\\_tbuf\\_log\(\)](#), [fiasco\\_tbuf\\_log\\_3val\(\)](#), [fiasco\\_tbuf\\_log\\_binary\(\)](#), [L4Re::Util::Event\\_t< Default\\_event\\_payload >::init\(\)](#), [l4\\_vcon\\_write\\_u\(\)](#), [L4Re::Util::Event\\_buffer\\_consumer\\_t< Default\\_event\\_payload >::process\(\)](#), and [L4virtio::Driver::Virtio\\_net\\_device::setup\\_device\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 13.1.9.7.3.2 l4\_ipc\_error()

```

l4_umword_t l4_ipc_error (
    l4_msgtag_t tag,
    l4_utcb_t * utcb) [inline]
  
```

Get the IPC error code for an IPC operation.

### Parameters

<i>tag</i>	Message tag returned by the IPC operation.
<i>utcb</i>	UTCB that was used for the IPC operation.

### Returns

0 if no error condition is set, error code otherwise (see [l4\\_ipc\\_tcr\\_error\\_t](#)).

### Examples

[examples/sys/ipc/ipc\\_example.c](#), and [examples/sys/start-with-exc/main.c](#).

Definition at line 633 of file [ipc.h](#).


References [L4\\_IPC\\_ERROR\\_MASK](#), [L4\\_LIKELY](#), [l4\\_msgtag\\_has\\_error\(\)](#), and [L4\\_NOTHROW](#).

Referenced by [l4util\\_ioport\\_map\(\)](#), [L4Re::Util::Event\\_buffer\\_consumer\\_t< Default\\_event\\_payload >::process\(\)](#), and [L4virtio::Driver::Device::wait\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



#### 13.1.9.7.3.3 l4\_ipc\_error\_code()

```
int l4_ipc_error_code (  
    l4_utcb_t * utcb)    [inline]
```

Get the error condition of the last invocation from the TCR.

##### Precondition

`l4_msgtag_has_error(tag) == true`

##### Parameters

<i>utcb</i>	UTCB to check.
-------------	----------------

##### Returns

Error condition of type [l4\\_ipc\\_tcr\\_error\\_t](#).

Definition at line 662 of file [ipc.h](#).

References [L4\\_INLINE](#), [L4\\_IPC\\_ERROR\\_MASK](#), and [L4\\_NOTHROW](#).

#### 13.1.9.7.3.4 l4\_ipc\_is\_rcv\_error()

```
int l4_ipc_is_rcv_error (  
    l4_utcb_t * utcb)    [inline]
```

Returns whether an error occurred in receive phase of an invocation.

##### Precondition

`l4_msgtag_has_error(tag) == true`

##### Parameters

<i>utcb</i>	UTCB to check.
-------------	----------------

##### Returns

Boolean value.

Definition at line 659 of file [ipc.h](#).

References [L4\\_INLINE](#), and [L4\\_NOTHROW](#).

#### 13.1.9.7.3.5 l4\_ipc\_is\_snd\_error()

```
int l4_ipc_is_snd_error (  
    l4_utcb_t * utcb) [inline]
```

Returns whether an error occurred in send phase of an invocation.

##### Precondition

`l4_msgtag_has_error(tag) == true`

##### Parameters

<i>utcb</i>	UTCB to check.
-------------	----------------

##### Returns


Boolean value.

Definition at line 656 of file [ipc.h](#).

References [L4\\_INLINE](#), and [L4\\_NOTHROW](#).

#### 13.1.9.8 Realtime API

Collaboration diagram for Realtime API:



#### 13.1.9.9 Message Tag

API related to the message tag data type.

Collaboration diagram for Message Tag:



## Data Structures

- struct [l4\\_msgtag\\_t](#)  
*Message tag data structure.*

## Enumerations

- enum [L4\\_platform\\_ctl\\_proto](#) { [L4\\_PROTO\\_PLATFORM\\_CTL](#) = 0 }  
*Predefined protocol type for messages to platform-control objects.*
- enum [L4\\_msgtag\\_protocol](#) {  
[L4\\_PROTO\\_NONE](#) = 0 , [L4\\_PROTO\\_ALLOW\\_SYSCALL](#) = 1 , [L4\\_PROTO\\_PF\\_EXCEPTION](#) = 1 ,  
[L4\\_PROTO\\_IRQ](#) = -1L ,  
[L4\\_PROTO\\_PAGE\\_FAULT](#) = -2L , [L4\\_PROTO\\_EXCEPTION](#) = -5L , [L4\\_PROTO\\_SIGMA0](#) = -6L ,  
[L4\\_PROTO\\_IO\\_PAGE\\_FAULT](#) = -8L ,  
[L4\\_PROTO\\_THREAD\\_GROUP](#) = -9L , [L4\\_PROTO\\_KOBJECT](#) = -10L , [L4\\_PROTO\\_TASK](#) = -11L ,  
[L4\\_PROTO\\_THREAD](#) = -12L ,  
[L4\\_PROTO\\_LOG](#) = -13L , [L4\\_PROTO\\_SCHEDULER](#) = -14L , [L4\\_PROTO\\_FACTORY](#) = -15L ,  
[L4\\_PROTO\\_VM](#) = -16L ,  
[L4\\_PROTO\\_DMA\\_SPACE](#) = -17L , [L4\\_PROTO\\_IRQ\\_SENDER](#) = -18L , [L4\\_PROTO\\_SEMAPHORE](#) = -20L ,  
[L4\\_PROTO\\_META](#) = -21L ,  
[L4\\_PROTO\\_IOMMU](#) = -22L , [L4\\_PROTO\\_DEBUGGER](#) = -23L , [L4\\_PROTO\\_SMCCC](#) = -24L ,  
[L4\\_PROTO\\_VCPU\\_CONTEXT](#) = -25L }  
*Message tag for IPC operations.*
- enum [L4\\_msgtag\\_flags](#) { [L4\\_MSGTAG\\_ERROR](#) , [L4\\_MSGTAG\\_TRANSFER\\_FPU](#) , [L4\\_MSGTAG\\_SCHEDULE](#) ,  
[L4\\_MSGTAG\\_PROPAGATE](#) = 0x4000 , [L4\\_MSGTAG\\_FLAGS](#) }  
*Flags for message tags.*

## Functions

- long [l4\\_msgtag\\_label](#) ([l4\\_msgtag\\_t](#)) [L4\\_NOTHROW](#)  
*Get the protocol of tag.*
- unsigned [l4\\_msgtag\\_words](#) ([l4\\_msgtag\\_t](#)) [L4\\_NOTHROW](#)  
*Get the number of untyped words.*
- unsigned [l4\\_msgtag\\_items](#) ([l4\\_msgtag\\_t](#)) [L4\\_NOTHROW](#)  
*Get the number of typed items.*
- unsigned [l4\\_msgtag\\_flags](#) ([l4\\_msgtag\\_t](#)) [L4\\_NOTHROW](#)  
*Get the flags.*
- unsigned [l4\\_msgtag\\_has\\_error](#) ([l4\\_msgtag\\_t](#)) [L4\\_NOTHROW](#)  
*Test for error indicator flag.*
- unsigned [l4\\_msgtag\\_is\\_page\\_fault](#) ([l4\\_msgtag\\_t](#)) [L4\\_NOTHROW](#)  
*Test for page-fault protocol.*
- unsigned [l4\\_msgtag\\_is\\_exception](#) ([l4\\_msgtag\\_t](#)) [L4\\_NOTHROW](#)  
*Test for exception protocol.*
- unsigned [l4\\_msgtag\\_is\\_sigma0](#) ([l4\\_msgtag\\_t](#)) [L4\\_NOTHROW](#)  
*Test for sigma0 protocol.*
- unsigned [l4\\_msgtag\\_is\\_io\\_page\\_fault](#) ([l4\\_msgtag\\_t](#)) [L4\\_NOTHROW](#)  
*Test for IO-page-fault protocol.*
- [l4\\_msgtag\\_t](#) [l4\\_msgtag](#) (long label, unsigned words, unsigned items, unsigned flags) [L4\\_NOTHROW](#)  
*Create a message tag from the specified values.*

### 13.1.9.9.1 Detailed Description

API related to the message tag data type.

#### Include File

```
#include <l4/sys/types.h>
```

### 13.1.9.9.2 Enumeration Type Documentation

#### 13.1.9.9.2.1 L4\_msgtag\_flags

```
enum L4_msgtag_flags
```

Flags for message tags.

#### Enumerator

L4_MSGTAG_ERROR	Error indicator flag.
L4_MSGTAG_TRANSFER_FPU	Enable FPU transfer flag for IPC. By enabling this flag when sending IPC, the sender indicates that the contents of the FPU shall be transferred to the receiving thread. However, the receiver has to indicate its willingness to receive FPU context in its buffer descriptor register (BDR).
L4_MSGTAG_SCHEDULE	Enable schedule in IPC flag. Usually IPC operations donate the remaining time slice of a thread to the called thread. Enabling this flag when sending IPC does a real scheduling decision. However, this flag decreases IPC performance.
L4_MSGTAG_FLAGS	Mask for all flags.

Definition at line 100 of file [types.h](#).

#### 13.1.9.9.2.2 L4\_msgtag\_protocol

```
enum L4_msgtag_protocol
```

Message tag for IPC operations.

All predefined protocols used by the kernel.

#### Enumerator

L4_PROTO_NONE	Default protocol tag to reply to kernel.
L4_PROTO_ALLOW_SYSCALL	Allow an alien the system call.
L4_PROTO_PF_EXCEPTION	Make an exception out of a page fault.
L4_PROTO_IRQ	IRQ message.
L4_PROTO_PAGE_FAULT	Page fault message.

L4_PROTO_EXCEPTION	Exception.
L4_PROTO_SIGMA0	Sigma0 protocol.
L4_PROTO_IO_PAGE_FAULT	I/O page fault message.
L4_PROTO_THREAD_GROUP	Protocol for messages to a thread group obj.
L4_PROTO_KOBJECT	Protocol for messages to a generic kobject.
L4_PROTO_TASK	Protocol for messages to a task object.
L4_PROTO_THREAD	Protocol for messages to a thread object.
L4_PROTO_LOG	Protocol for messages to a log object.
L4_PROTO_SCHEDULER	Protocol for messages to a scheduler object.
L4_PROTO_FACTORY	Protocol for messages to a factory object.
L4_PROTO_VM	Protocol for messages to a virtual machine object.
L4_PROTO_DMA_SPACE	Protocol for (creating) kernel DMA space objects.
L4_PROTO_IRQ_SENDER	Protocol for IRQ senders (IRQ -> IPC).
L4_PROTO_SEMAPHORE	Protocol for semaphore objects.
L4_PROTO_META	Meta information protocol.
L4_PROTO_IOMMU	Protocol ID for IO-MMUs.
L4_PROTO_DEBUGGER	Protocol ID for the debugger.
L4_PROTO_SMCCC	Protocol ID for ARM SMCCC calls.
L4_PROTO_VCPU_CONTEXT	Protocol for hardware vCPU contexts.

Definition at line 52 of file [types.h](#).

#### 13.1.9.9.2.3 L4\_platform\_ctl\_proto

```
enum L4_platform_ctl_proto
```

Predefined protocol type for messages to platform-control objects.

##### Enumerator

L4_PROTO_PLATFORM_CTL	Protocol messages to a platform control object. See <a href="#">L4_platform_ctl_ops</a> for allowed operations.
-----------------------	---

Definition at line 174 of file [platform\\_control.h](#).

#### 13.1.9.9.3 Function Documentation

##### 13.1.9.9.3.1 l4\_msgtag()

```
l4_msgtag_t l4_msgtag (
    long label,
    unsigned words,
    unsigned items,
    unsigned flags) [inline]
```



Create a message tag from the specified values.

Message tag functions.

## Parameters

<i>label</i>	The user-defined label
<i>words</i>	The number of untyped words within the UTCB
<i>items</i>	The number of typed items (e.g., flexpages) within the UTCB
<i>flags</i>	The IPC flags for realtime and FPU extensions

## Returns

Message tag

## Examples


examples/sys/aliens/main.c, examples/sys/ipc/ipc\_example.c, examples/sys/singlestep/main.c, examples/sys/start-with-exo/main.c, and examples/sys/utcb-ipc/main.c.

Definition at line 421 of file types.h.

References [L4\\_NOTHROW](#).

Referenced by [\\_\\_l4\\_kdebug\\_3\\_text\(\)](#), [\\_\\_l4\\_kdebug\\_op\(\)](#), [\\_\\_l4\\_kdebug\\_op\\_1\(\)](#), [\\_\\_l4\\_kdebug\\_text\(\)](#), [L4::Irqp\\_t< Derived, BASE, boost::asio::ip::udp::endpoint, boost::asio::basic\\_stream\\_socket< boost::asio::ip::udp::endpoint, boost::asio::basic\\_stream\\_protocol>>, boost::asio::streambuf, boost::asio::detail::executor\\_type, boost::asio::detail::strand\\_executor\\_handler, boost::asio::detail::thread\\_type>](#), [fiasco\\_amd64\\_segment\\_info\(\)](#), [fiasco\\_amd64\\_set\\_fs\(\)](#), [fiasco\\_amd64\\_set\\_segment\\_base\(\)](#), [fiasco\\_gdt\\_get\\_entry\\_offset\(\)](#), [fiasco\\_gdt\\_set\(\)](#), [fiasco\\_ldt\\_set\(\)](#), [L4::Server< LOOP\\_HOOKS >::internal\\_loop\(\)](#), [l4\\_icu\\_bind\\_u\(\)](#), [l4\\_icu\\_info\\_u\(\)](#), [l4\\_icu\\_msi\\_info\\_u\(\)](#), [l4\\_icu\\_set\\_mode\\_u\(\)](#), [l4\\_icu\\_unbind\\_u\(\)](#), [l4\\_irq\\_bind\\_vcpu\\_u\(\)](#), [l4\\_irq\\_detach\\_u\(\)](#), [l4\\_irq\\_receive\\_u\(\)](#), [l4\\_irq\\_trigger\\_u\(\)](#), [l4\\_irq\\_unmask\\_u\(\)](#), [l4\\_irq\\_wait\\_u\(\)](#), [l4\\_kd\\_enter\(\)](#), [l4\\_thread\\_ex\\_regs\\_u\(\)](#), [l4\\_thread\\_vcpu\\_control\\_ext\\_u\(\)](#), [l4\\_thread\\_vcpu\\_control\\_u\(\)](#), [l4\\_thread\\_yield\(\)](#), [l4\\_vcon\\_get\\_attr\\_u\(\)](#), [l4\\_vcon\\_send\\_u\(\)](#), [l4\\_vcon\\_set\\_attr\\_u\(\)](#), [l4util\\_ioport\\_map\(\)](#), [L4::Thread::modify\\_senders\(\)](#), [L4::Ipc\\_svr::Dbg\\_dispatch< R, Exc, Printer >::operator\(\)\(\)](#), [L4::Ipc\\_svr::Exc\\_dispatch< R, Exc >::operator\(\)\(\)](#), [L4::Cap\\_base::validate\(\)](#), and [L4::Cap\\_base::validate\(\)](#).

Here is the caller graph for this function:



### 13.1.9.9.3.2 l4\_msgtag\_flags()

```
unsigned l4_msgtag_flags (
    l4_msgtag_t t) [inline]
```

Get the flags.

The flag are defined by [L4\\_msgtag\\_flags](#).

#### Parameters

<i>t</i>	The tag
----------	---------

#### Returns

Flags

Definition at line 451 of file [types.h](#).

References [L4\\_NOTHROW](#).

Referenced by [l4\\_msgtag\\_t::flags\(\)](#).

Here is the caller graph for this function:



#### 13.1.9.9.3.3 l4\_msgtag\_has\_error()

```
unsigned l4_msgtag_has_error (  
    l4\_msgtag\_t t) [inline]
```

Test for error indicator flag.

#### Parameters

<i>t</i>	The tag
----------	---------

#### Returns

>0 for yes, 0 for no

Return whether the kernel operation caused a communication error, e.g. with IPC. if true: `utcb->error` is valid, otherwise `utcb->error` is not valid

#### Examples

[examples/sys/aliens/main.c](#), [examples/sys/singlestep/main.c](#), and [examples/sys/utcb-ipc/main.c](#).



Here is the call graph for this function:



Here is the caller graph for this function:



#### 13.1.9.9.3.5 l4\_msgtag\_is\_io\_page\_fault()

```
unsigned l4_msgtag_is_io_page_fault (  
    l4_msgtag_t t) [inline]
```

Test for IO-page-fault protocol.

##### Parameters

<i>t</i>	The tag
----------	---------

##### Returns


Boolean value

Definition at line 470 of file [types.h](#).


References [L4\\_INLINE](#), [l4\\_msgtag\\_label\(\)](#), [L4\\_NOTHROW](#), and [L4\\_PROTO\\_IO\\_PAGE\\_FAULT](#).

Referenced by [l4\\_msgtag\\_t::is\\_io\\_page\\_fault\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



#### 13.1.9.9.3.6 l4\_msgtag\_is\_page\_fault()

```

unsigned l4_msgtag_is_page_fault (
    l4_msgtag_t t) [inline]
  
```

Test for page-fault protocol.

##### Parameters

<i>t</i>	The tag
----------	---------

##### Returns


Boolean value

Definition at line 461 of file [types.h](#).


References [L4\\_INLINE](#), [l4\\_msgtag\\_label\(\)](#), [L4\\_NOTHROW](#), and [L4\\_PROTO\\_PAGE\\_FAULT](#).

Referenced by [l4\\_msgtag\\_t::is\\_page\\_fault\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



#### 13.1.9.3.7 l4\_msgtag\_is\_sigma0()

```
unsigned l4_msgtag_is_sigma0 (  
    l4_msgtag_t t) [inline]
```

Test for sigma0 protocol.

##### Parameters

<i>t</i>	The tag
----------	---------

##### Returns

Boolean value

Definition at line 467 of file [types.h](#).

References [L4\\_INLINE](#), [l4\\_msgtag\\_label\(\)](#), [L4\\_NOTHROW](#), and [L4\\_PROTO\\_SIGMA0](#).

Referenced by [l4\\_msgtag\\_t::is\\_sigma0\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



#### 13.1.9.9.3.8 l4\_msgtag\_items()

```
unsigned l4_msgtag_items (  
    l4_msgtag_t t) [inline]
```

Get the number of typed items.

##### Parameters

<i>t</i>	The tag
----------	---------

##### Returns


Number of items.

Definition at line 447 of file [types.h](#).

References [L4\\_NOTHROW](#).

Referenced by [l4\\_msgtag\\_t::items\(\)](#), and [l4util\\_ioport\\_map\(\)](#).

Here is the caller graph for this function:



#### 13.1.9.9.3.9 l4\_msgtag\_label()

```
long l4_msgtag_label (  
    l4_msgtag_t t) [inline]
```

Get the protocol of tag.

##### Parameters

<i>t</i>	The tag
----------	---------



**Returns**

Label

**Examples**


[examples/sys/singlestep/main.c](#), and [examples/sys/start-with-exc/main.c](#).

Definition at line 433 of file [types.h](#).

References [L4\\_NOTHROW](#).

Referenced by [l4\\_msgtag\\_is\\_exception\(\)](#), [l4\\_msgtag\\_is\\_io\\_page\\_fault\(\)](#), [l4\\_msgtag\\_is\\_page\\_fault\(\)](#), [l4\\_msgtag\\_is\\_sigma0\(\)](#), and [l4\\_msgtag\\_t::label\(\)](#).

Here is the caller graph for this function:

**13.1.9.9.3.10 l4\_msgtag\_words()**

```
unsigned l4_msgtag_words (
    l4_msgtag_t t) [inline]
```

Get the number of untyped words.

**Parameters**

<i>t</i>	The tag
----------	---------

**Returns**

Number of words

**Examples**


[examples/sys/utcb-ipc/main.c](#).

Definition at line 443 of file [types.h](#).

References [L4\\_NOTHROW](#).

Referenced by [l4\\_icu\\_msi\\_info\\_u\(\)](#), and [l4\\_msgtag\\_t::words\(\)](#).


Here is the caller graph for this function:



### 13.1.9.10 Virtual Registers (UTCBS)

[L4 Virtual Registers \(UTCBS\)](#).

Collaboration diagram for Virtual Registers (UTCBS):



## Topics

- [Message Registers \(MRs\)](#) . . . . . 265
- [Buffer Registers \(BRs\)](#) . . . . . 269
- [Thread Control Registers \(TCRs\)](#) . . . . . 270
- [ARM Virtual Registers \(UTCB\)](#) . . . . . 271
- [ARM64 Virtual Registers \(UTCB\)](#) . . . . . 271
- [AMD64 Virtual Registers \(UTCB\)](#) . . . . . 272
- [x86 Virtual Registers \(UTCB\)](#) . . . . . 272

## Files

- file [utcb.h](#)  
*UTCB definitions for ARM.*
- file [utcb.h](#)  
*UTCB definitions for ARM64.*
- file [utcb.h](#)  
*UTCB definitions for AMD64.*
- file [utcb.h](#)  
*UTCB definitions for x86.*

## Typedefs

- typedef struct [l4\\_utcb\\_t](#) [l4\\_utcb\\_t](#)  
*Opaque type for the UTCB.*

## Functions

- [l4\\_utcb\\_t](#) \* [l4\\_utcb](#) (void) [L4\\_NOTHROW](#) [L4\\_PURE](#)  
*Get the UTCB address.*
- [l4\\_msg\\_regs\\_t](#) \* [l4\\_utcb\\_mr](#) (void) [L4\\_NOTHROW](#) [L4\\_PURE](#)  
*Get the message-register block of a UTCB.*
- [l4\\_buf\\_regs\\_t](#) \* [l4\\_utcb\\_br](#) (void) [L4\\_NOTHROW](#) [L4\\_PURE](#)  
*Get the buffer-register block of a UTCB.*
- [l4\\_thread\\_regs\\_t](#) \* [l4\\_utcb\\_tcr](#) (void) [L4\\_NOTHROW](#) [L4\\_PURE](#)  
*Get the thread-control-register block of a UTCB.*

### 13.1.9.10.1 Detailed Description

[L4](#) Virtual Registers (UTCB).

#### Include File

```
#include <l4/sys/utcb.h>
```

The virtual registers are part of the micro-kernel API and are located in the user-level thread control block (UTCB). The UTCB is a data structure defined by the micro kernel and located on kernel-provided memory. Each [L4](#) thread gets a unique UTCB assigned when it is bound to a task (see [Thread Control](#) , [l4\\_thread\\_control\\_bind\(\)](#) for more information).

The UTCB is arranged in three blocks of virtual registers.

- [Thread Control Registers \(TCRs\)](#)
- [Message Registers \(MRs\)](#)
- [Buffer Registers \(BRs\)](#)

To access the contents of the virtual registers the [l4\\_utcb\\_mr\(\)](#), [l4\\_utcb\\_tcr\(\)](#), and [l4\\_utcb\\_br\(\)](#) functions must be used.

### 13.1.9.10.2 Typedef Documentation

#### 13.1.9.10.2.1 [l4\\_utcb\\_t](#)

```
typedef struct l4_utcb_t l4_utcb_t
```

Opaque type for the UTCB.

To access the contents of the virtual registers the [l4\\_utcb\\_mr\(\)](#), [l4\\_utcb\\_tcr\(\)](#), and [l4\\_utcb\\_br\(\)](#) functions must be used.

#### Examples

[examples/sys/aliens/main.c](#), [examples/sys/singlestep/main.c](#), [examples/sys/start-with-exc/main.c](#), and [examples/sys/utcb-ipc/main.c](#).

Definition at line 56 of file [utcb.h](#).

### 13.1.9.10.3 Function Documentation

#### 13.1.9.10.3.1 l4\_utcb\_br()

```
l4_buf_regs_t * l4_utcb_br (  
    void )    [inline]
```

Get the buffer-register block of a UTCB.

##### Returns

A pointer to the buffer-register block of `u`.

Definition at line 364 of file `utcb.h`.


References [L4\\_INLINE](#), [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Referenced by [l4util\\_ioport\\_map\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



#### 13.1.9.10.3.2 l4\_utcb\_mr()

```
l4_msg_regs_t * l4_utcb_mr (  
    void )    [inline]
```

Get the message-register block of a UTCB.

### Returns

A pointer to the message-register block of `u`.

### Examples

[examples/sys/aliens/main.c](#), [examples/sys/ipc/ipc\\_example.c](#), [examples/sys/singlestep/main.c](#), and [examples/sys/utcb-ipc/main.c](#).

Definition at line 361 of file [utcb.h](#).

References [L4\\_INLINE](#), [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Referenced by [l4util\\_ioport\\_map\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



#### 13.1.9.10.3.3 l4\_utcb\_tcr()

```
l4_thread_regs_t * l4_utcb_tcr (  
    void ) [inline]
```

Get the thread-control-register block of a UTCB.

**Returns**

A pointer to the thread-control-register block of `u`.

Definition at line 367 of file `utcb.h`.

References [L4\\_INLINE](#), [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:

**13.1.9.10.4 Message Registers (MRs)**

Collaboration diagram for Message Registers (MRs):

**Topics**

- [Exception registers](#) . . . . . 266  
*Overly definition of the MRs for exception messages.*

**Data Structures**

- union [l4\\_msg\\_regs\\_t](#)  
*Encapsulation of the message-register block in the UTCB.*

**Typedefs**


- typedef union `l4_msg_regs_t` **`l4_msg_regs_t`**  
*Encapsulation of the message-register block in the UTCB.*

### 13.1.9.10.4.1 Detailed Description

### 13.1.9.10.4.2 Exception registers

Overly definition of the MRs for exception messages.

Collaboration diagram for Exception registers:



## Functions

- `l4_umword_t l4_utcb_exc_pc (l4_exc_regs_t const *u) L4_NOTHROW L4_PURE`  
Access function to get the program counter of the exception state.
- `void l4_utcb_exc_pc_set (l4_exc_regs_t *u, l4_addr_t pc) L4_NOTHROW`  
Set the program counter register in the exception state.
- `unsigned long l4_utcb_exc_typeval (l4_exc_regs_t const *u) L4_NOTHROW L4_PURE`  
Get the value out of an exception UTCB that describes the type of exception.
- `int l4_utcb_exc_is_pf (l4_exc_regs_t const *u) L4_NOTHROW L4_PURE`  
Check whether an exception IPC is a page fault.
- `l4_addr_t l4_utcb_exc_pfa (l4_exc_regs_t const *u) L4_NOTHROW L4_PURE`  
Function to get the L4 style page fault address out of an exception.
- `int l4_utcb_exc_is_ex_regs_exception (l4_exc_regs_t const *u) L4_NOTHROW L4_PURE`  
Check whether an exception IPC was triggered via `l4_thread_ex_regs()`.
- `l4_exc_regs_t * l4_utcb_exc (void) L4_NOTHROW L4_PURE`  
Get the message-register block of a UTCB (for an exception IPC).

## Detailed Description

Overly definition of the MRs for exception messages.

## Function Documentation

### `l4_utcb_exc()`

```
l4_exc_regs_t * l4_utcb_exc (
    void ) [inline]
```

Get the message-register block of a UTCB (for an exception IPC).



**Returns**

A pointer to the exception message in `u`.


**Examples**

[examples/sys/aliens/main.c](#), and [examples/sys/singlestep/main.c](#).

Definition at line 370 of file `utcb.h`.

References [L4\\_INLINE](#), [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:

**`l4_utcb_exc_is_ex_regs_exception()`**

```
int l4_utcb_exc_is_ex_regs_exception (
    l4_exc_regs_t const * u) [inline]
```

Check whether an exception IPC was triggered via [l4\\_thread\\_ex\\_regs\(\)](#).

**Return values**

<code>0</code>	Exception was not triggered through <code>ex_regs</code> .
<code>!=0</code>	Exception was triggered through <code>ex_regs</code> .

This function checks if the exception was emitted by using the `L4_THREAD_EX_REGS_TRIGGER_EXCEPTION` flag in an [l4\\_thread\\_ex\\_regs\(\)](#) call.

Definition at line 100 of file `utcb.h`.

References [L4\\_INLINE](#), [L4\\_NOTHROW](#), and [l4\\_utcb\\_exc\\_typeval\(\)](#).

Here is the call graph for this function:



### **l4\_utcb\_exc\_is\_pf()**

```
int l4_utcb_exc_is_pf (
    l4_exc_regs_t const * u) [inline]
```

Check whether an exception IPC is a page fault.

#### **Returns**

0 if not, != 0 if yes

Function to check whether an exception IPC is a page fault, also applies to I/O pagefaults.

Definition at line 90 of file [utcb.h](#).

References [L4\\_INLINE](#), and [L4\\_NOTHROW](#).

### **l4\_utcb\_exc\_pc()**

```
l4_umword_t l4_utcb_exc_pc (
    l4_exc_regs_t const * u) [inline]
```

Access function to get the program counter of the exception state.

#### **Parameters**

<i>u</i>	UTCB
----------	------

#### **Returns**

The program counter register out of the exception state.

#### **Examples**

[examples/sys/aliens/main.c](#), and [examples/sys/singlestep/main.c](#).

Definition at line 75 of file [utcb.h](#).

References [L4\\_INLINE](#), and [L4\\_NOTHROW](#).

**l4\_utcb\_exc\_pc\_set()**

```
void l4_utcb_exc_pc_set (
    l4_exc_regs_t * u,
    l4_addr_t pc) [inline]
```

Set the program counter register in the exception state.

**Parameters**


<i>u</i>	UTCB
<i>pc</i>	The program counter to set.

Definition at line 80 of file [utcb.h](#).

References [L4\\_INLINE](#), and [L4\\_NOTHROW](#).

**13.1.9.10.5 Buffer Registers (BRs)**

Collaboration diagram for Buffer Registers (BRs):

**Data Structures**

- struct [l4\\_buf\\_regs\\_t](#)  
*Encapsulation of the buffer-registers block in the UTCB.*

**Typedefs**

- typedef struct [l4\\_buf\\_regs\\_t](#) **l4\_buf\_regs\_t**  
*Encapsulation of the buffer-registers block in the UTCB.*

**Enumerations**

- enum [l4\\_buffer\\_desc\\_consts\\_t](#) { [L4\\_BDR\\_MEM\\_SHIFT](#) = 0 , [L4\\_BDR\\_IO\\_SHIFT](#) = 5 , [L4\\_BDR\\_OBJ\\_SHIFT](#) = 10 , [L4\\_BDR\\_OFFSET\\_MASK](#) = (1UL << 20) - 1 }
- Constants for buffer descriptors.*

## Functions

- void **I4\_utcb\_inherit\_fpu** (int switch\_on) [L4\\_NOTHROW](#)  
*Enable or disable inheritance of FPU state to receiver.*

### 13.1.9.10.5.1 Detailed Description

### 13.1.9.10.5.2 Enumeration Type Documentation

#### **I4\_buffer\_desc\_consts\_t**

enum [I4\\_buffer\\_desc\\_consts\\_t](#)

Constants for buffer descriptors.


#### Enumerator

L4_BDR_MEM_SHIFT	Bit offset for the memory-buffer index.
L4_BDR_IO_SHIFT	Bit offset for the IO-buffer index.
L4_BDR_OBJ_SHIFT	Bit offset for the capability-buffer index.

Definition at line [301](#) of file [consts.h](#).

### 13.1.9.10.6 Thread Control Registers (TCRs)

Collaboration diagram for Thread Control Registers (TCRs):



## Data Structures

- struct [I4\\_thread\\_regs\\_t](#)  
*Encapsulation of the thread-control-register block of the UTCB.*


## Typedefs

- typedef struct I4\_thread\_regs\_t **I4\_thread\_regs\_t**  
*Encapsulation of the thread-control-register block of the UTCB.*

### 13.1.9.10.6.1 Detailed Description

### 13.1.9.10.7 ARM Virtual Registers (UTCB)

Collaboration diagram for ARM Virtual Registers (UTCB):




### Data Structures

- struct [l4\\_exc\\_regs\\_t](#)  
*UTCB structure for exceptions.*

### 13.1.9.10.7.1 Detailed Description

### 13.1.9.10.8 ARM64 Virtual Registers (UTCB)

Collaboration diagram for ARM64 Virtual Registers (UTCB):




### Data Structures

- struct [l4\\_exc\\_regs\\_t](#)  
*UTCB structure for exceptions.*

### 13.1.9.10.8.1 Detailed Description

### 13.1.9.10.9 AMD64 Virtual Registers (UTCB)

Collaboration diagram for AMD64 Virtual Registers (UTCB):




### Data Structures

- struct [l4\\_exc\\_regs\\_t](#)  
*UTCB structure for exceptions.*

### 13.1.9.10.9.1 Detailed Description

### 13.1.9.10.10 x86 Virtual Registers (UTCB)

Collaboration diagram for x86 Virtual Registers (UTCB):



### Data Structures


- struct [l4\\_exc\\_regs\\_t](#)  
*UTCB structure for exceptions.*

### 13.1.9.10.10.1 Detailed Description

## 13.1.10 Kernel Objects

API of kernel objects.

Collaboration diagram for Kernel Objects:



## Topics

- IPC-Gate API ..... 275  
*The C IPC gate interface, see [L4::lpc\\_gate](#) for the C++ interface.*

•		
DMA space	280	<i>A DMA space represents a device memory address space managed by an IOMMU.</i>
•		
L4 kernel object type information	280	<i>Type information for <a href="#">L4</a> server objects that can be called via IPC.</i>
•		
Factory•	282	<i>C factory interface to create objects, see <a href="#">L4::Factory</a> for the C++ interface.</i>
•		
Virtual Machines	293	<i>Virtual Machine API.</i>
•		
Interrupt controller	314	<i>The C <a href="#">lcu</a> interface, see <a href="#">L4::lcu</a> for the C++ interface.</i>
•		
IRQs •	331	<i>C IRQ interface, see <a href="#">L4::lrq</a> for the C++ interface.</i>
•		
Platform Control C API	346	<i>C interface for controlling platform-wide properties, see <a href="#">L4::Platform_control</a> for the C++ interface.</i>
•		
Scheduler	352	<i>C interface of the Scheduler kernel object, see <a href="#">L4::Scheduler</a> for the C++ interface.</i>
•		
Kernel-provided semaphore	360	<i>C semaphore interface, see <a href="#">L4::Semaphore</a> for the C++ interface.</i>
•		
Task •	362	<i>C interface of the Task kernel object, see <a href="#">L4::Task</a> for the C++ interface.</i>
•		
Thread•	374	<i>C Thread object interface, see <a href="#">L4::Thread</a> for the C++ interface.</i>
•		
Thread groups	408	<i>C thread group interface, see <a href="#">L4::Thread_group</a> for the C++ interface.</i>
•		
Virtual Console	410	<i>C Virtual console interface for simple character based input and output, see <a href="#">L4::Vcon</a> for the C++ interface.</i>

## Data Structures

- class [L4::Kobject](#)  
*Base class for all kinds of kernel objects and remote objects, referenced by capabilities.*
- class [L4::Vm](#)  
*Virtual machine host address space.*



### 13.1.10.1 Detailed Description

API of kernel objects.


#### Include File

```
#include <l4/sys/kernel_object.h>
```

### 13.1.10.2 IPC-Gate API

The C IPC gate interface, see [L4::lpc\\_gate](#) for the C++ interface.

Collaboration diagram for IPC-Gate API:



#### Functions

- [l4\\_msgtag\\_t l4\\_ipc\\_gate\\_get\\_infos](#) ([l4\\_cap\\_idx\\_t](#) gate, [l4\\_umword\\_t](#) \*label)  
*Get information about the IPC-gate.*
- [l4\\_msgtag\\_t l4\\_rcv\\_ep\\_bind\\_thread](#) ([l4\\_cap\\_idx\\_t](#) ep, [l4\\_cap\\_idx\\_t](#) thread, [l4\\_umword\\_t](#) label)  
*Bind the IPC receive endpoint to a thread.*
- [l4\\_msgtag\\_t l4\\_rcv\\_ep\\_bind\\_snd\\_destination](#) ([l4\\_cap\\_idx\\_t](#) ep, [l4\\_cap\\_idx\\_t](#) snd\_dst, [l4\\_umword\\_t](#) label)  
*Bind the IPC receive endpoint to a send destination (a thread).*

#### 13.1.10.2.1 Detailed Description

The C IPC gate interface, see [L4::lpc\\_gate](#) for the C++ interface.

IPC gates are used to create secure communication channels between protection domains. An IPC gate can be created using the [Factory](#) interface.

Depending on the permissions of the capability used, an IPC gate forwards IPC to the [Thread](#) the IPC gate is *bound* to (cf. [l4\\_rcv\\_ep\\_bind\\_thread\(\)](#) and [l4\\_rcv\\_ep\\_bind\\_snd\\_destination\(\)](#)). If the capability has the [L4\\_FPAGE\\_C\\_IPCGATE\\_SVR](#) permission, only IPC using a protocol different from the [L4\\_PROTO\\_KOBJECT](#) protocol is forwarded. Without the [L4\\_FPAGE\\_C\\_IPCGATE\\_SVR](#) permission, all IPC is forwarded. The latter is the usual case for a client in a client/server scenario. When not bound to a thread or thread group yet, the forwarded IPC blocks until the IPC gate is bound to a thread or thread group, or the IPC times out.

Forwarded IPC is always forwarded to the userland of the thread the IPC gate is bound to, either directly or indirectly using a thread group. That means, the [Thread](#) interface of that thread is not accessible via an IPC gate. The [IPC-Gate API](#) of an IPC gate is only accessible if the capability used has the [L4\\_FPAGE\\_C\\_IPCGATE\\_SVR](#) permission (cf. previous paragraph). Conversely that means, if the capability used lacks the [L4\\_FPAGE\\_C\\_IPCGATE\\_SVR](#) permission, [IPC-Gate API](#) calls are forwarded to the thread or thread group the IPC gate is bound to instead of being

processed by the IPC gate itself. In a client/server scenario, a client should only get IPC gate capabilities without [L4\\_FPAGE\\_C\\_IPCGATE\\_SVR](#) permission so the client cannot tamper with the IPC gate.

When binding an IPC gate to a thread or thread group, a user-defined, kernel protected, machine-word sized payload called the IPC gate's *label* is assigned to the IPC gate (note that the two least significant bits of the label must be zero; cf. [l4\\_rcv\\_ep\\_bind\\_thread\(\)](#) and [l4\\_rcv\\_ep\\_bind\\_snd\\_destination\(\)](#)). When a send-only IPC or call IPC is forwarded via an IPC gate, the label provided by the sender is ignored and replaced by the IPC gate's label where the two least significant bits are set to the [L4\\_CAP\\_FPAGE\\_S](#) and [L4\\_CAP\\_FPAGE\\_W](#) permissions of the capability used. The replaced label is only visible to the thread the IPC gate is bound to upon receive (or to the selected thread from the thread group the IPC gate is bound to). However, the configured label of an IPC gate can also be queried via [l4\\_ipc\\_gate\\_get\\_infos\(\)](#) if the capability used has the [L4\\_FPAGE\\_C\\_IPCGATE\\_SVR](#) permission.

When deleting an IPC gate or when unbinding it from a thread or thread group, the label of IPC already in flight won't be changed. To ensure that no IPC from this IPC gate is received by a thread with an unexpected label, [l4\\_thread\\_modify\\_sender\\_start\(\)](#) shall be used to change the labels of every pending IPC to that gate. This is also required if the label of an already bound IPC gate is changed. It is not necessary after binding the IPC gate to a thread or thread group for the first time.

When binding a currently bound IPC gate to a new thread or thread group, the same label should be used that was used with the old thread. Otherwise the old and the new thread need to synchronize to avoid IPC messages with unexpected labels.

#### Include File

```
#include <l4/sys/ipc_gate.h>
```

For the C++ interface refer to the [L4::ipc\\_gate](#) documentation.

#### See also

[Object Invocation](#)

### 13.1.10.2.2 Function Documentation

#### 13.1.10.2.2.1 l4\_ipc\_gate\_get\_infos()

```
l4_msgtag_t l4_ipc_gate_get_infos (
    l4_cap_idx_t gate,
    l4_umword_t * label) [inline]
```

Get information about the IPC-gate.

#### Parameters

	<i>gate</i>	The IPC gate object to get information about.
out	<i>label</i>	The label of the IPC gate is returned here.

#### Returns

System call return tag.


**Precondition**

If `gate` does not possess the [L4\\_FPAGE\\_C\\_IPCGATE\\_SVR](#) right, the kernel will not perform this operation. Instead, the underlying IPC message will be forwarded to the thread or thread group the IPC gate is bound to, blocking the caller if the IPC gate is not bound yet.

Definition at line 166 of file [ipc\\_gate.h](#).

References [l4\\_utcb\(\)](#).

Here is the call graph for this function:

**13.1.10.2.2.2 l4\_rcv\_ep\_bind\_snd\_destination()**

```

l4_msgtag_t l4_rcv_ep_bind_snd_destination (
    l4_cap_idx_t ep,
    l4_cap_idx_t snd_dst,
    l4_umword_t label) [inline]
  
```

Bind the IPC receive endpoint to a send destination (a thread).

**Parameters**

<i>ep</i>	The IPC receive endpoint object.
<i>snd_dst</i>	The send destination (thread) object <i>ep</i> shall be bound to.
<i>label</i>	Label to assign to <i>ep</i> . For IPC gates, the two least significant bits must be set to zero.

**Returns**

Syscall return tag containing one of the following return codes.

**Return values**

<i>L4_EOK</i>	Operation successful.
<i>-L4_EINVAL</i>	<i>snd_dst</i> is not a thread object or other arguments were malformed.
<i>-L4_EPERM</i>	No <a href="#">L4_CAP_FPAGE_S</a> right on <i>ep</i> or <i>snd_dst</i> .

**Precondition**

If `ep` is an IPC gate capability without the `L4_FPAGE_C_IPCGATE_SVR` right, the kernel will not perform this operation. Instead, the underlying IPC message will be forwarded to the send destination the IPC gate is bound to, blocking the caller if the IPC gate was not bound yet.


The specified `label` is passed to the receiver of the incoming IPC. It is possible to re-bind a receive endpoint to the same or a different send destination. In this case, IPC already in flight will be delivered with the old label to the previously bound thread unless `l4_thread_modify_sender_start()` is used to change these labels.

Definition at line 138 of file `rcv_endpoint.h`.

References `l4_utcb()`.

Referenced by `L4::Rcv_endpoint::bind_snd_destination()`.

Here is the call graph for this function:



Here is the caller graph for this function:

**13.1.10.2.2.3 l4\_rcv\_ep\_bind\_thread()**

```

l4_msgtag_t l4_rcv_ep_bind_thread (
    l4_cap_idx_t ep,
    l4_cap_idx_t thread,
    l4_umword_t label) [inline]
  
```

Bind the IPC receive endpoint to a thread.

### Parameters

<i>ep</i>	The IPC receive endpoint object.
<i>thread</i>	The thread object <i>ep</i> shall be bound to.
<i>label</i>	Label to assign to <i>ep</i> . For IPC gates, the two least significant bits must be set to zero.

### Returns

Syscall return tag containing one of the following return codes.

### Return values

<i>L4_EOK</i>	Operation successful.
<i>-L4_EINVAL</i>	<i>thread</i> is not a thread object or other arguments were malformed.
<i>-L4_EPERM</i>	Insufficient permissions; see precondition.

### Precondition

The capabilities *ep* and *thread* both must have the permission [L4\\_CAP\\_FPAGE\\_S](#).

If *ep* is an IPC gate capability without the [L4\\_FPAGE\\_C\\_IPCGATE\\_SVR](#) right, the kernel will not perform this operation. Instead, the underlying IPC message will be forwarded to the thread the IPC gate is bound to, blocking the caller if the IPC gate was not bound yet.

The specified *label* is passed to the receiver of the incoming IPC. It is possible to re-bind a receive endpoint to the same or a different thread. In this case, IPC already in flight will be delivered with the old label to the previously bound thread unless [l4\\_thread\\_modify\\_sender\\_start\(\)](#) is used to change these labels.

### Examples

[examples/sys/isr/main.c](#).

Definition at line 131 of file [rcv\\_endpoint.h](#).

References [l4\\_utcb\(\)](#).


Here is the call graph for this function:



### 13.1.10.3 DMA space

A DMA space represents a device memory address space managed by an IOMMU.

Collaboration diagram for DMA space:



A DMA space represents a device memory address space managed by an IOMMU.

That is, it manages the translation of virtual addresses used by devices to physical addresses. It is accessed via the [L4::Task](#) interface, but with the following caveats:

- No threads can be bound to it.
- No objects (and IO ports on IA32) can be mapped to it.
- No kernel-user memory can be added to it.
- It must be constructed by passing the `L4_PROTO_DMA_SPACE` protocol constant to the kernel factory's [L4::Factory.create\(\)](#) call.


A DMA space must be bound to an [L4::iommu](#) to enable the address translation for specific devices.

The kernel factory allows to create DMA spaces only if the kernel has been configured with IOMMU support and if an IOMMU was detected.

### 13.1.10.4 L4 kernel object type information

Type information for [L4](#) server objects that can be called via IPC.

Collaboration diagram for L4 kernel object type information:



## Data Structures

- struct [L4::Type\\_info](#)  
*Dynamic Type Information for [L4Re](#) Interfaces.*
- struct [L4::Kobject\\_typeid](#)< T >  
*Meta object for handling access to type information of Kobjects.*
- class [L4::Kobject\\_t](#)< Derived, Base, PROTO, S\_DEMAND >  
*Helper class to create an [L4Re](#) interface class that is derived from a single base class.*
- class [L4::Kobject\\_2t](#)< Derived, Base1, Base2, PROTO, S\_DEMAND >  
*Helper class to create an [L4Re](#) interface class that is derived from two base classes (see [L4::Kobject\\_t](#)).*
- struct [L4::Kobject\\_3t](#)< Derived, Base1, Base2, Base3, PROTO, S\_DEMAND >  
*Helper class to create an [L4Re](#) interface class that is derived from three base classes (see [L4::Kobject\\_t](#)).*
- struct [L4::Kobject\\_x](#)< Derived, ARGS >  
*Generic [Kobject](#) inheritance template.*

## Functions

- template<typename T>  
[Type\\_info](#) const \* [L4::kobject\\_typeid](#) () noexcept  
*Get the [L4::Type\\_info](#) for the [L4Re](#) interface given in T.*

### 13.1.10.4.1 Detailed Description

Type information for [L4](#) server objects that can be called via IPC.

This type information consists of inheritance information, the protocol number assigned to an interface as well as the demand on server-side resources.

### 13.1.10.4.2 Function Documentation

#### 13.1.10.4.2.1 kobject\_typeid()

```
template<typename T>
Type\_info const * L4::kobject\_typeid () [inline], [noexcept]
```

Get the [L4::Type\\_info](#) for the [L4Re](#) interface given in T.

## Template Parameters

<a href="#">T</a>	The type ( <a href="#">L4Re</a> interface) for which the information shall be returned.
-------------------	---

**Returns**


A pointer to the [L4::Type\\_info](#) structure for T.

Definition at line 682 of file [\\_\\_typeinfo.h](#).

References [L4::Kobject\\_typeid< T >::id\(\)](#).

Referenced by [cap\\_dynamic\\_cast\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 13.1.10.5 Factory

C factory interface to create objects, see [L4::Factory](#) for the C++ interface.

Collaboration diagram for Factory:





## Functions

- [l4\\_msgtag\\_t l4\\_factory\\_create\\_task](#) ([l4\\_cap\\_idx\\_t](#) factory, [l4\\_cap\\_idx\\_t](#) target\_cap, [l4\\_fpage\\_t](#) \*utcb\_area) [L4\\_NOTHROW](#)  
*Create a new task.*
- [l4\\_msgtag\\_t l4\\_factory\\_create\\_thread](#) ([l4\\_cap\\_idx\\_t](#) factory, [l4\\_cap\\_idx\\_t](#) target\_cap) [L4\\_NOTHROW](#)  
*Create a new thread.*
- [l4\\_msgtag\\_t l4\\_factory\\_create\\_factory](#) ([l4\\_cap\\_idx\\_t](#) factory, [l4\\_cap\\_idx\\_t](#) target\_cap, unsigned long limit) [L4\\_NOTHROW](#)  
*Create a new factory.*
- [l4\\_msgtag\\_t l4\\_factory\\_create\\_gate](#) ([l4\\_cap\\_idx\\_t](#) factory, [l4\\_cap\\_idx\\_t](#) target\_cap, [l4\\_cap\\_idx\\_t](#) snd\_dst\_↔ cap, [l4\\_umword\\_t](#) label) [L4\\_NOTHROW](#)  
*Create a new IPC gate, optionally bound to a send destination (a thread or thread group).*
- [l4\\_msgtag\\_t l4\\_factory\\_create\\_irq](#) ([l4\\_cap\\_idx\\_t](#) factory, [l4\\_cap\\_idx\\_t](#) target\_cap) [L4\\_NOTHROW](#)  
*Create a new IRQ sender.*
- [l4\\_msgtag\\_t l4\\_factory\\_create\\_vm](#) ([l4\\_cap\\_idx\\_t](#) factory, [l4\\_cap\\_idx\\_t](#) target\_cap) [L4\\_NOTHROW](#)  
*Create a new virtual machine.*
- [l4\\_msgtag\\_t l4\\_factory\\_create\\_vcpu\\_context](#) ([l4\\_cap\\_idx\\_t](#) factory, [l4\\_cap\\_idx\\_t](#) target\_cap) [L4\\_NOTHROW](#)  
*Create a new vCPU context.*
- [l4\\_msgtag\\_t l4\\_factory\\_create\\_thread\\_group](#) ([l4\\_cap\\_idx\\_t](#) factory, [l4\\_cap\\_idx\\_t](#) target\_cap, unsigned policy) [L4\\_NOTHROW](#)  
*Create a new thread group.*
- [l4\\_msgtag\\_t l4\\_factory\\_create](#) ([l4\\_cap\\_idx\\_t](#) factory, long obj, [l4\\_cap\\_idx\\_t](#) target) [L4\\_NOTHROW](#)  
*Create a new object.*

### 13.1.10.5.1 Detailed Description

C factory interface to create objects, see [L4::Factory](#) for the C++ interface.

A factory is used to create all kinds of kernel objects:

- [Task](#)
- [Thread](#)
- [Factory](#)
- [IPC-Gate API](#)
- [IRQs](#)
- [Virtual Machines](#)

To create a new kernel object the caller has to specify the factory to use for creation. The caller has to allocate a capability slot where the kernel stores the new object's capability.

The factory is equipped with a limit that limits the amount of kernel memory available for that factory.

#### Note

The limit does not give any guarantee for the amount of available kernel memory.

#### Include File

```
#include <l4/sys/factory.h>
```

For the C++ interface refer to [L4::Factory](#).

### 13.1.10.5.2 Function Documentation

#### 13.1.10.5.2.1 l4\_factory\_create()

```
l4_msgtag_t l4_factory_create (
    l4_cap_idx_t factory,
    long obj,
    l4_cap_idx_t target) [inline]
```

Create a new object.

#### Parameters

	<i>factory</i>	Factory to use for creation.
	<i>obj</i>	Protocol ID to describe the type of the object to create.
out	<i>target</i>	The kernel stores the new objects's capability into this slot.

#### Return values

<i>L4_EOK</i>	No error occurred.
<i>-L4_EPERM</i>	Insufficient permissions; see precondition.
<i>&lt;0</i>	Error code.


#### Precondition

The capability *factory* must have the permission [L4\\_CAP\\_FPAGE\\_S](#).

Definition at line 707 of file [factory.h](#).

References [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:



### 13.1.10.5.2.2 l4\_factory\_create\_factory()

```
l4_msgtag_t l4_factory_create_factory (
    l4_cap_idx_t factory,
    l4_cap_idx_t target_cap,
    unsigned long limit) [inline]
```

Create a new factory.

#### Parameters

	<i>factory</i>	Capability selector for factory to use for creation.
out	<i>target_cap</i>	The kernel stores the new factory's capability into this slot.
	<i>limit</i>	Limit for the new factory in bytes.

#### Returns

Syscall return tag

#### Return values

<i>L4_EOK</i>	No error occurred.
<i>-L4_EPERM</i>	Insufficient permissions; see precondition.
<i>&lt;0</i>	Error code.

#### Precondition

The capability *factory* must have the permission [L4\\_CAP\\_FPAGE\\_S](#).

#### Note


The limit of the new factory is subtracted from the available amount of the factory used for creation.

This method is only guaranteed to work with the [Kernel Factory](#). For other services, use the generic [L4::Factory::create\(\)](#) method and consult the service documentation for information on the arguments that need to be passed to the create stream.

Definition at line 545 of file [factory.h](#).

References [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:



### 13.1.10.5.2.3 l4\_factory\_create\_gate()

```
l4_msgtag_t l4_factory_create_gate (
    l4_cap_idx_t factory,
    l4_cap_idx_t target_cap,
    l4_cap_idx_t snd_dst_cap,
    l4_umword_t label) [inline]
```

Create a new IPC gate, optionally bound to a send destination (a thread or thread group).

#### Parameters

	<i>factory</i>	Capability selector for factory to use for creation.
out	<i>target_cap</i>	The kernel stores the new IPC gate's capability into this slot.
	<i>snd_dst_cap</i>	Optional capability selector of a thread or thread group to bind the gate to. Use <a href="#">L4_INVALID_CAP</a> to create an unbound IPC gate.
	<i>label</i>	Optional label of the gate (precisely used if <i>snd_dst_cap</i> is valid). If <i>snd_dst_cap</i> is valid, <i>label</i> must be present.

#### Returns

Syscall return tag containing one of the following return codes.

#### Return values

<i>L4_EOK</i>	No error occurred.
<i>-L4_ENOMEM</i>	Out-of-memory during allocation of the <i>lpc_gate</i> object.
<i>-L4_EINVAL</i>	<i>snd_dst_cap</i> is void or points to something that is not a thread or thread group.
<i>-L4_EPERM</i>	Insufficient permissions; see precondition.

#### Precondition

The capability *factory* must have the permission [L4\\_CAP\\_FPAGE\\_S](#). Also *snd\_dst\_cap* (if not [L4\\_INVALID\\_CAP](#)) must have the permission [L4\\_CAP\\_FPAGE\\_S](#).

An unbound IPC gate can be bound to a thread using [l4\\_rcv\\_ep\\_bind\\_thread\(\)](#).


See also

[IPC-Gate API](#)

Definition at line 553 of file [factory.h](#).

References [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:



#### 13.1.10.5.2.4 l4\_factory\_create\_irq()

```
l4_msgtag_t l4_factory_create_irq (
    l4_cap_idx_t factory,
    l4_cap_idx_t target_cap) [inline]
```

Create a new IRQ sender.

##### Parameters

	<i>factory</i>	Factory to use for creation.
out	<i>target_cap</i>	The kernel stores the new IRQ's capability into this slot.

##### Return values

<i>L4_EOK</i>	No error occurred.
<i>-L4_EPERM</i>	Insufficient permissions; see precondition.
<i>&lt;0</i>	Error code.

##### Precondition

The capability *factory* must have the permission [L4\\_CAP\\_FPAGE\\_S](#).

##### See also

[IRQs](#)


##### Examples

[examples/sys/isr/main.c](#).

Definition at line [561](#) of file [factory.h](#).

References [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:



### 13.1.10.5.2.5 l4\_factory\_create\_task()

```
l4_msgtag_t l4_factory_create_task (
    l4_cap_idx_t factory,
    l4_cap_idx_t target_cap,
    l4_fpage_t * utcb_area) [inline]
```

Create a new task.

#### Parameters

	<i>factory</i>	Capability selector for factory to use for creation.
out	<i>target_cap</i>	The kernel stores the new task's capability into this slot.
in, out	<i>utcb_area</i>	Pointer to flexpage that describes an area of kernel-user memory that can be used for UTCBs and vCPU state-save-areas of the new task.

On systems without MMU, the flexpage is adjusted to reflect the actually allocated physical address.

#### Returns

Syscall return tag.

#### Return values

<i>L4_EOK</i>	No error occurred.
<i>-L4_EPERM</i>	Insufficient permissions; see precondition.
<i>&lt;0</i>	Error code.

#### Precondition

The capability *factory* must have the permission [L4\\_CAP\\_FPAGE\\_S](#).

#### Note

The size of the UTCB area specifies indirectly the number of UTCBs available for this task. Refer to [l4\\_task\\_add\\_ku\\_mem\(\)](#) for adding more of this type of memory.


#### See also

[Task](#)

Definition at line 531 of file [factory.h](#).

References [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:



**13.1.10.5.2.6 l4\_factory\_create\_thread()**

```
l4_msgtag_t l4_factory_create_thread (
    l4_cap_idx_t factory,
    l4_cap_idx_t target_cap) [inline]
```

Create a new thread.

**Parameters**

	<i>factory</i>	Capability selector for factory to use for creation.
out	<i>target_cap</i>	The kernel stores the new thread's capability into this slot.

**Returns**

Syscall return tag

**Return values**

<i>L4_EOK</i>	No error occurred.
<i>-L4_EPERM</i>	Insufficient permissions; see precondition.
<i>&lt; 0</i>	Error code.

**Precondition**

The capability *factory* must have the permission [L4\\_CAP\\_FPAGE\\_S](#).

**See also**

[Thread](#)


**Examples**

[examples/sys/aliens/main.c](#), [examples/sys/singlestep/main.c](#), [examples/sys/start-with-exc/main.c](#), and [examples/sys/utcb-ipc/main.c](#).

Definition at line [538](#) of file [factory.h](#).

References [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:



### 13.1.10.5.2.7 l4\_factory\_create\_thread\_group()

```
l4_msgtag_t l4_factory_create_thread_group (
    l4_cap_idx_t factory,
    l4_cap_idx_t target_cap,
    unsigned policy) [inline]
```

Create a new thread group.

An IPC endpoint can be bound to a thread group. When a message arrives at the IPC endpoint, a specific thread of the thread group is selected to actually receive the message. A thread group is a send destination for an IPC endpoint.

#### Parameters

	<i>factory</i>	Capability selector for factory to use for creation.
out	<i>target_cap</i>	The kernel stores the new thread group's capability into this slot.
	<i>policy</i>	Policy parameter for the thread group. See #L4_thread_group_policy for a list of supported values.

#### Returns

Syscall return tag

#### Return values

<i>L4_EOK</i>	No error occurred.
<i>-L4_ENOMEM</i>	Out-of-memory during allocation of the thread group object.
<i>-L4_EINVAL</i>	Invalid policy parameter.
<i>-L4_EPERM</i>	The <code>factory</code> instance requires <code>L4_CAP_FPAGE_S</code> rights on <code>factory</code> and <code>L4_CAP_FPAGE_S</code> is not present.
<i>&lt;0</i>	Error code.


#### See also

[Thread groups](#)

Definition at line 582 of file [factory.h](#).

References [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:





#### 13.1.10.5.2.8 l4\_factory\_create\_vcpu\_context()

```
l4_msgtag_t l4_factory_create_vcpu_context (
    l4_cap_idx_t factory,
    l4_cap_idx_t target_cap) [inline]
```

Create a new vCPU context.

A vCPU context typically represents a hardware structure that captures the state of a vCPU on a CPU (e.g. VMX VMCS).

##### Parameters

	<i>factory</i>	Capability selector for factory to use for creation.
out	<i>target_cap</i>	The kernel stores the new vCPU context's capability into this slot.

##### Returns

Syscall return tag

##### Return values

<i>L4_EOK</i>	No error occurred.
<i>-L4_EPERM</i>	Insufficient permissions; see precondition.
<i>&lt;0</i>	Error code.

##### Precondition

The capability *factory* must have the permission [L4\\_CAP\\_FPAGE\\_S](#).


##### See also

[Virtual Machines](#)

Definition at line [575](#) of file [factory.h](#).

References [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:



#### 13.1.10.5.2.9 l4\_factory\_create\_vm()

```
l4_msgtag_t l4_factory_create_vm (  
    l4_cap_idx_t factory,  
    l4_cap_idx_t target_cap) [inline]
```

Create a new virtual machine.

##### Parameters

	<i>factory</i>	Capability selector for factory to use for creation.
out	<i>target_cap</i>	The kernel stores the new VM's capability into this slot.

##### Returns

Syscall return tag

##### Return values

<i>L4_EOK</i>	No error occurred.
<i>-L4_EPERM</i>	Insufficient permissions; see precondition.
<i>&lt;0</i>	Error code.

##### Precondition

The capability *factory* must have the permission [L4\\_CAP\\_FPAGE\\_S](#).


##### See also

[Virtual Machines](#)

Definition at line [568](#) of file [factory.h](#).

References [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).


Here is the call graph for this function:



### 13.1.10.6 Virtual Machines

Virtual Machine API.

Collaboration diagram for Virtual Machines:



#### Topics

- VM API for SVM . . . . . [293](#)  
*Virtual machine API for SVM.*
- VM API for VMX . . . . . [294](#)  
*Virtual machine API for VMX.*
- VM API for TZ . . . . . [314](#)  
*Virtual Machine API for ARM TrustZone.*

#### 13.1.10.6.1 Detailed Description

Virtual Machine API.

#### 13.1.10.6.2 VM API for SVM

Virtual machine API for SVM.

Collaboration diagram for VM API for SVM:



## Data Structures

- struct [l4\\_vm\\_svm\\_vmcb\\_control\\_area](#)  
*VMCB structure for SVM VMs.*
- struct [l4\\_vm\\_svm\\_vmcb\\_state\\_save\\_area\\_seg](#)  
*State save area segment selector struct.*
- struct [l4\\_vm\\_svm\\_vmcb\\_state\\_save\\_area](#)  
*State save area structure for SVM VMs.*
- struct [l4\\_vm\\_svm\\_vmcb\\_t](#)  
*Control structure for SVM VMs.*

## Typedefs

- typedef struct [l4\\_vm\\_svm\\_vmcb\\_control\\_area](#) [l4\\_vm\\_svm\\_vmcb\\_control\\_area\\_t](#)  
*VMCB structure for SVM VMs.*
- typedef struct [l4\\_vm\\_svm\\_vmcb\\_state\\_save\\_area\\_seg](#) [l4\\_vm\\_svm\\_vmcb\\_state\\_save\\_area\\_seg\\_t](#)  
*State save area segment selector struct.*
- typedef struct [l4\\_vm\\_svm\\_vmcb\\_state\\_save\\_area](#) [l4\\_vm\\_svm\\_vmcb\\_state\\_save\\_area\\_t](#)  
*State save area structure for SVM VMs.*
- typedef struct [l4\\_vm\\_svm\\_vmcb\\_t](#) [l4\\_vm\\_svm\\_vmcb\\_t](#)  
*Control structure for SVM VMs.*

### 13.1.10.6.2.1 Detailed Description

Virtual machine API for SVM.

### 13.1.10.6.3 VM API for VMX

Virtual machine API for VMX.

Collaboration diagram for VM API for VMX:



## Data Structures

- struct [l4\\_vmx\\_offset\\_table\\_t](#)  
*Software VMCS field offset table.*
- struct [l4\\_vm\\_vmx\\_vcpu\\_vmcs\\_t](#)  
*VMX software VMCS.*
- struct [l4\\_vm\\_vmx\\_vcpu\\_infos\\_t](#)  
*VMX information members.*
- struct [l4\\_vm\\_vmx\\_vcpu\\_state\\_t](#)  
*VMX vCPU state.*

## Typedefs

- typedef struct l4\_vmx\_offset\_table\_t [l4\\_vmx\\_offset\\_table\\_t](#)  
*Software VMCS field offset table.*
- typedef struct l4\_vm\_vmx\_vcpu\_vmcs\_t [l4\\_vm\\_vmx\\_vcpu\\_vmcs\\_t](#)  
*VMX software VMCS.*
- typedef struct l4\_vm\_vmx\_vcpu\_infos\_t [l4\\_vm\\_vmx\\_vcpu\\_infos\\_t](#)  
*VMX information members.*
- typedef struct l4\_vm\_vmx\_vcpu\_state\_t [l4\\_vm\\_vmx\\_vcpu\\_state\\_t](#)  
*VMX vCPU state.*

## Enumerations

- enum [l4\\_vm\\_vmx\\_caps\\_regs](#) {  
[L4\\_VM\\_VMX\\_BASIC\\_REG](#) = 0 , [L4\\_VM\\_VMX\\_TRUE\\_PINBASED\\_CTLS\\_REG](#) = 1 , [L4\\_VM\\_VMX\\_TRUE\\_PROCBASED\\_CTLS\\_REG](#) = 2 , [L4\\_VM\\_VMX\\_TRUE\\_EXIT\\_CTLS\\_REG](#) = 3 ,  
[L4\\_VM\\_VMX\\_TRUE\\_ENTRY\\_CTLS\\_REG](#) = 4 , [L4\\_VM\\_VMX\\_MISC\\_REG](#) = 5 , [L4\\_VM\\_VMX\\_CR0\\_FIXED0\\_REG](#) = 6 , [L4\\_VM\\_VMX\\_CR0\\_FIXED1\\_REG](#) = 7 ,  
[L4\\_VM\\_VMX\\_CR4\\_FIXED0\\_REG](#) = 8 , [L4\\_VM\\_VMX\\_CR4\\_FIXED1\\_REG](#) = 9 , [L4\\_VM\\_VMX\\_VMCS\\_ENUM\\_REG](#) = 10 , [L4\\_VM\\_VMX\\_PROCBASED\\_CTLS2\\_REG](#) = 11 ,  
[L4\\_VM\\_VMX\\_EPT\\_VPID\\_CAP\\_REG](#) = 12 , [L4\\_VM\\_VMX\\_NESTED\\_REVISION](#) = 13 , [L4\\_VM\\_VMX\\_NUM\\_CAPS\\_REGS](#)  
}
  
*Exported VMX capability registers.*
- enum [l4\\_vm\\_vmx\\_dfl1\\_regs](#) {  
[L4\\_VM\\_VMX\\_PINBASED\\_CTLS\\_DFL1\\_REG](#) = 0 , [L4\\_VM\\_VMX\\_PROCBASED\\_CTLS\\_DFL1\\_REG](#) = 1 ,  
[L4\\_VM\\_VMX\\_EXIT\\_CTLS\\_DFL1\\_REG](#) = 2 , [L4\\_VM\\_VMX\\_ENTRY\\_CTLS\\_DFL1\\_REG](#) = 3 ,  
[L4\\_VM\\_VMX\\_NUM\\_DFL1\\_REGS](#) }
  
*Exported VMX capability registers (default to 1 bits).*
- enum [l4\\_vm\\_vmx\\_sw\\_fields](#) {  
[L4\\_VM\\_VMX\\_VMCS\\_CR2](#) = 0x6880 , [L4\\_VM\\_VMX\\_VMCS\\_NAT\\_ARG0](#) = 0x6882 , [L4\\_VM\\_VMX\\_VMCS\\_NAT\\_ARG1](#) = 0x6884 , [L4\\_VM\\_VMX\\_VMCS\\_NAT\\_ARG2](#) = 0x6886 ,  
[L4\\_VM\\_VMX\\_VMCS\\_NAT\\_ARG3](#) = 0x6888 , [L4\\_VM\\_VMX\\_VMCS\\_XCR0](#) = 0x2880 , [L4\\_VM\\_VMX\\_VMCS\\_MSR\\_SYSCALL\\_MSR](#) = 0x2882 , [L4\\_VM\\_VMX\\_VMCS\\_MSR\\_LSTAR](#) = 0x2884 ,  
[L4\\_VM\\_VMX\\_VMCS\\_MSR\\_CSTAR](#) = 0x2886 , [L4\\_VM\\_VMX\\_VMCS\\_MSR\\_TSC\\_AUX](#) = 0x2888 ,  
[L4\\_VM\\_VMX\\_VMCS\\_MSR\\_STAR](#) = 0x288a , [L4\\_VM\\_VMX\\_VMCS\\_MSR\\_KERNEL\\_GS\\_BASE](#) = 0x288c }
  
*Additional (software-defined) VMCS fields.*
- enum [l4\\_vm\\_vmx\\_vmcs\\_sizes](#) { [L4\\_VM\\_VMX\\_VMCS\\_SIZE\\_VALUES](#) = 2560 , [L4\\_VM\\_VMX\\_VMCS\\_SIZE\\_DIRTY\\_BITMAP](#) = 320 }
  
*Sizes of software VMCS members.*

## Functions

- [l4\\_uint64\\_t l4\\_vm\\_vmx\\_get\\_caps](#) ([l4\\_vm\\_vmx\\_vcpu\\_state\\_t](#) const \*vcpu\_state, enum [l4\\_vm\\_vmx\\_caps\\_regs](#) caps\_reg) [L4\\_NOTHROW](#)  
*Get a capability register for VMX.*
- [l4\\_uint32\\_t l4\\_vm\\_vmx\\_get\\_caps\\_default1](#) ([l4\\_vm\\_vmx\\_vcpu\\_state\\_t](#) const \*vcpu\_state, enum [l4\\_vm\\_vmx\\_dfl1\\_regs](#) dfl1\_reg) [L4\\_NOTHROW](#)  
*Get a default to one capability register for VMX.*
- unsigned [l4\\_vm\\_vmx\\_field\\_len](#) (unsigned field) [L4\\_NOTHROW](#)  
*Return length in bytes of a VMCS field.*
- unsigned [l4\\_vm\\_vmx\\_field\\_order](#) (unsigned field) [L4\\_NOTHROW](#)  
*Return length in power of two (bytes) of a VMCS field.*

- `void l4_vm_vmx_clear (l4_vm_vmx_vcpu_vmcs_t *vmcs, l4_vm_vmx_vcpu_vmcs_t *dest_vmcs) L4_NOTHROW`  
*Save the content from the software VMCS to a different software VMCS.*
- `void l4_vm_vmx_ptr_load (l4_vm_vmx_vcpu_vmcs_t *vmcs, l4_vm_vmx_vcpu_vmcs_t *src_vmcs) L4_NOTHROW`  
*Load the content from a different software VMCS to the software VMCS.*
- `l4_uint32_t l4_vm_vmx_get_cr2_index (l4_vm_vmx_vcpu_vmcs_t const *vmcs) L4_NOTHROW`  
*Get the software VMCS field index of the virtual CR2 register.*
- `l4_umword_t l4_vm_vmx_read_nat (l4_vm_vmx_vcpu_vmcs_t *vmcs, unsigned field) L4_NOTHROW`  
*Read a natural-width software VMCS field.*
- `l4_uint16_t l4_vm_vmx_read_16 (l4_vm_vmx_vcpu_vmcs_t *vmcs, unsigned field) L4_NOTHROW`  
*Read a 16-bit software VMCS field.*
- `l4_uint32_t l4_vm_vmx_read_32 (l4_vm_vmx_vcpu_vmcs_t *vmcs, unsigned field) L4_NOTHROW`  
*Read a 32-bit software VMCS field.*
- `l4_uint64_t l4_vm_vmx_read_64 (l4_vm_vmx_vcpu_vmcs_t *vmcs, unsigned field) L4_NOTHROW`  
*Read a 64-bit software VMCS field.*
- `l4_uint64_t l4_vm_vmx_read (l4_vm_vmx_vcpu_vmcs_t *vmcs, unsigned field) L4_NOTHROW`  
*Read any software VMCS field.*
- `void l4_vm_vmx_write_nat (l4_vm_vmx_vcpu_vmcs_t *vmcs, unsigned field, l4_umword_t val) L4_NOTHROW`  
*Write to a natural-width software VMCS field.*
- `void l4_vm_vmx_write_16 (l4_vm_vmx_vcpu_vmcs_t *vmcs, unsigned field, l4_uint16_t val) L4_NOTHROW`  
*Write to a 16-bit software VMCS field.*
- `void l4_vm_vmx_write_32 (l4_vm_vmx_vcpu_vmcs_t *vmcs, unsigned field, l4_uint32_t val) L4_NOTHROW`  
*Write to a 32-bit software VMCS field.*
- `void l4_vm_vmx_write_64 (l4_vm_vmx_vcpu_vmcs_t *vmcs, unsigned field, l4_uint64_t val) L4_NOTHROW`  
*Write to a 64-bit software VMCS field.*
- `void l4_vm_vmx_write (l4_vm_vmx_vcpu_vmcs_t *vmcs, unsigned field, l4_uint64_t val) L4_NOTHROW`  
*Write to an arbitrary software VMCS field.*
- `void l4_vm_vmx_set_hw_vmcs (l4_vm_vmx_vcpu_vmcs_t *vmcs, l4_cap_idx_t vmcs_cap) L4_NOTHROW`  
*Associate the software VMCS with a vCPU context, i.e.*
- `l4_cap_idx_t l4_vm_vmx_get_hw_vmcs (l4_vm_vmx_vcpu_vmcs_t *vmcs) L4_NOTHROW`  
*Get the vCPU context (i.e.*

### 13.1.10.6.3.1 Detailed Description

Virtual machine API for VMX.

### 13.1.10.6.3.2 Typedef Documentation

#### `l4_vm_vmx_vcpu_state_t`

```
typedef struct l4_vm_vmx_vcpu_state_t l4_vm_vmx_vcpu_state_t
```

VMX vCPU state.

This is a specialization of the generic vCPU state for VMX. This data structure represents the following memory layout:

- 0x000 - 0x1ff: Standard vCPU state (with padding). See [l4\\_vcpu\\_state\\_t](#).
- 0x200 - 0x3ff: VMX information members (with padding). See [l4\\_vm\\_vmx\\_vcpu\\_infos\\_t](#).
- 0x400 - 0xffff: VMX software VMCS. See [l4\\_vm\\_vmx\\_vcpu\\_vmcs\\_t](#).

**Note**

The memory layout is documented here for reference purposes. However, the users are strongly discouraged from accessing the data structure directly. The API functions defined in this file are the preferred way of achieving the functionality.

**l4\_vm\_vmx\_vcpu\_vmcs\_t**

```
typedef struct l4_vm_vmx_vcpu_vmcs_t l4_vm_vmx_vcpu_vmcs_t
```

VMX software VMCS.

This data structure represents the following memory layout:

- 0x000 - 0x007: Reserved (ignored by the kernel). In the hardware VMCS, the revision identifier and the abort indicator are stored in this area. Hereby we simply ignore these two entries.
- 0x008 - 0x00f: User space data (ignored by the kernel). This currently stores the pointer to a different software VMCS whose content has been loaded to this software VMCS.
- 0x010 - 0x013: VMCS field index of the software-defined CR2 field in the software VMCS.
- 0x014 - 0x017: Reserved.
- 0x018 - 0x01f: Capability of the vCPU context, i.e. the hardware VMCS object (with padding).
- 0x020 - 0x047: Software VMCS field offset table. See [l4\\_vmx\\_offset\\_table\\_t](#).
- 0x048 - 0x0bf: Reserved.
- 0x0c0 - 0xabf: Software VMCS fields (with padding).
- 0xac0 - 0xbff: Software VMCS fields dirty bitmap (with padding).

**Note**

The memory layout is documented here for reference purposes. However, the users are strongly discouraged from accessing the data structure directly. The API functions defined in this file are the preferred way of achieving the functionality.

**l4\_vmx\_offset\_table\_t**

```
typedef struct l4_vmx_offset_table_t l4_vmx_offset_table_t
```

Software VMCS field offset table.

This data structure represents the following memory layout:

- 0x00 - 0x02: 3 offsets for 16-bit fields.
- 0x03: Reserved.
- 0x04 - 0x06: 3 offsets for 64-bit fields.
- 0x07: Reserved.
- 0x08 - 0x0a: 3 offsets for 32-bit fields.

- 0x0b: Reserved.
- 0x0c - 0x0e: 3 offsets for natural-width fields.
- 0x0f: Reserved.
- 0x10 - 0x12: 3 limits for 16-bit fields.
- 0x13: Reserved.
- 0x14 - 0x16: 3 limits for 64-bit fields.
- 0x17: Reserved.
- 0x18 - 0x1a: 3 limits for 32-bit fields.
- 0x1b: Reserved.
- 0x1c - 0x1e: 3 limits for natural-width fields.
- 0x1f: Reserved.
- 0x20 - 0x23: 4 index shifts.
- 0x24: Offset of the first software VMCS field.
- 0x25: Size of the software VMCS fields.
- 0x26 - 0x27: Reserved.

The offsets/limits in each size category are in the following order:

- Control fields.
- Read-only fields.
- Guest fields.

The index shifts are in the following order:

- 16-bit.
- 64-bit.
- 32-bit.
- Natural-width.

All offsets/limits/sizes are represented in a 64-byte granule.

The offsets (after being multiplied by 64) are indexes in the values array in [l4\\_vm\\_vmx\\_vcpu\\_vmcs\\_t](#) and bit indexes in the dirty\_bitmap array in [l4\\_vm\\_vmx\\_vcpu\\_vmcs\\_t](#).

The limits (after being multiplied by 64) represent the range of the available indexes.

#### Note

The memory layout is documented here for reference purposes. However, the users are strongly discouraged from accessing the data structure directly. The API functions defined in this file are the preferred way of achieving the functionality.



### 13.1.10.6.3.3 Enumeration Type Documentation

#### L4\_vm\_vmx\_caps\_regs

enum [L4\\_vm\\_vmx\\_caps\\_regs](#)

Exported VMX capability registers.

##### Enumerator

L4_VM_VMX_BASIC_REG	Basic VMX capabilities.
L4_VM_VMX_TRUE_PINBASED_CTLIS_REG	True pin-based control caps.
L4_VM_VMX_TRUE_PROCBASED_CTLIS_REG	True processor based control caps.
L4_VM_VMX_TRUE_EXIT_CTLIS_REG	True exit control caps.
L4_VM_VMX_TRUE_ENTRY_CTLIS_REG	True entry control caps.
L4_VM_VMX_MISC_REG	Misc caps.
L4_VM_VMX_CR0_FIXED0_REG	Fixed to 0 bits of CR0.
L4_VM_VMX_CR0_FIXED1_REG	Fixed to 1 bits of CR0.
L4_VM_VMX_CR4_FIXED0_REG	Fixed to 0 bits of CR4.
L4_VM_VMX_CR4_FIXED1_REG	Fixed to 1 bits of CR4.
L4_VM_VMX_VMCS_ENUM_REG	VMCS enumeration info.
L4_VM_VMX_PROCBASED_CTLIS2_REG	Processor based control 2 caps.
L4_VM_VMX_EPT_VPID_CAP_REG	EPT and VPID caps.
L4_VM_VMX_NESTED_REVISION	Nested VMCS revision.
L4_VM_VMX_NUM_CAPS_REGS	Total number of VMX capability registers.

Definition at line 28 of file [\\_\\_vm-vmx.h](#).

#### L4\_vm\_vmx\_dfl1\_regs

enum [L4\\_vm\\_vmx\\_dfl1\\_regs](#)

Exported VMX capability registers (default to 1 bits).

##### Enumerator

L4_VM_VMX_PINBASED_CTLIS_DFL1_REG	Default 1 bits in pin-based controls.
L4_VM_VMX_PROCBASED_CTLIS_DFL1_REG	Default 1 bits in processor-based controls.
L4_VM_VMX_EXIT_CTLIS_DFL1_REG	Default 1 bits in exit controls.
L4_VM_VMX_ENTRY_CTLIS_DFL1_REG	Default 1 bits in entry controls.
L4_VM_VMX_NUM_DFL1_REGS	Total number of default on registers.

Definition at line 51 of file [\\_\\_vm-vmx.h](#).

## L4\_vm\_vmx\_sw\_fields

```
enum L4_vm_vmx_sw_fields
```

Additional (software-defined) VMCS fields.

The VMCS offsets defined here are actually not in the hardware VMCS. However our VMMs run in user mode and need to have access to certain registers available in kernel mode only. So we put them into our software VMCS.

### Enumerator

L4_VM_VMX_VMCS_CR2	Software VMCS offset for CR2.  <b>Note</b>  You usually need to check this value against the value you get from <a href="#">l4_vm_vmx_get_cr2_index()</a> to make sure you are running on a compatible kernel.
L4_VM_VMX_VMCS_NAT_ARG0	Custom argument passed from kernel to user space.
L4_VM_VMX_VMCS_NAT_ARG1	Custom argument passed from kernel to user space.
L4_VM_VMX_VMCS_NAT_ARG2	Custom argument passed from kernel to user space.
L4_VM_VMX_VMCS_NAT_ARG3	Custom argument passed from kernel to user space.
L4_VM_VMX_VMCS_XCR0	VMCS offset of extended control register XCR0.
L4_VM_VMX_VMCS_MSR_SYSCALL_MASK	VMCS offset of system call flag mask MSR.
L4_VM_VMX_VMCS_MSR_LSTAR	VMCS offset of IA32e mode system call target address MSR.
L4_VM_VMX_VMCS_MSR_CSTAR	VMCS offset of IA32 mode system call target address MSR.
L4_VM_VMX_VMCS_MSR_TSC_AUX	VMCS offset of auxiliary TSC signature MSR.
L4_VM_VMX_VMCS_MSR_STAR	VMCS offset of system call target address MSR.
L4_VM_VMX_VMCS_MSR_KERNEL_GS_BASE	VMCS offset of GS base address swap target MSR.

Definition at line 69 of file [\\_\\_vm-vmx.h](#).

## L4\_vm\_vmx\_vmcs\_sizes

```
enum L4_vm_vmx_vmcs_sizes
```

Sizes of software VMCS members.

### Enumerator

L4_VM_VMX_VMCS_SIZE_VALUES	Size of the software VMCS values member.
L4_VM_VMX_VMCS_SIZE_DIRTY_BITMAP	Size of the software VMCS dirty bitmap member.

Definition at line 170 of file [\\_\\_vm-vmx.h](#).

#### 13.1.10.6.3.4 Function Documentation

##### **l4\_vm\_vmx\_clear()**

```
void l4_vm_vmx_clear (
    l4_vm_vmx_vcpu_vmcs_t * vmcs,
    l4_vm_vmx_vcpu_vmcs_t * dest_vmcs) [inline]
```

Save the content from the software VMCS to a different software VMCS.

##### **Parameters**

<i>vmcs</i>	Pointer to the source software VMCS.
<i>dest_vmcs</i>	Pointer to the destination software VMCS.


This function is comparable to the VMX VMCLEAR instruction.

Definition at line 698 of file [\\_\\_vm-vmx.h](#).

References [L4\\_NOTHROW](#), [l4\\_vm\\_vmx\\_get\\_hw\\_vmcs\(\)](#), [l4\\_vm\\_vmx\\_set\\_hw\\_vmcs\(\)](#), and [L4\\_VM\\_VMX\\_VMCS\\_SIZE\\_DIRTY\\_BITM](#)

Referenced by [l4\\_vm\\_vmx\\_ptr\\_load\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### **l4\_vm\_vmx\_field\_len()**

```
unsigned l4_vm_vmx_field_len (  
    unsigned field) [inline]
```

Return length in bytes of a VMCS field.

#### **Parameters**

<i>field</i>	Field number.
--------------	---------------


#### **Returns**

Width of field in bytes.

Definition at line 593 of file [\\_\\_vm-vmx.h](#).

References [L4\\_NOTHROW](#), and [l4\\_vm\\_vmx\\_field\\_order\(\)](#).

Here is the call graph for this function:



### **l4\_vm\_vmx\_field\_order()**

```
unsigned l4_vm_vmx_field_order (  
    unsigned field) [inline]
```

Return length in power of two (bytes) of a VMCS field.

#### **Parameters**

<i>field</i>	Field number.
--------------	---------------

**Returns**


Width of field in power of two (bytes).

Definition at line 600 of file [\\_\\_vm-vmx.h](#).

References [L4\\_NOTHROW](#).

Referenced by [l4\\_vm\\_vmx\\_field\\_len\(\)](#).

Here is the caller graph for this function:

**`l4_vm_vmx_get_caps()`**

```

l4_uint64_t l4_vm_vmx_get_caps (
    l4_vm_vmx_vcpu_state_t const * vcpu_state,
    enum L4_vm_vmx_caps_regs caps_reg) [inline]
  
```

Get a capability register for VMX.

**Parameters**

<i>vcpu_state</i>	Pointer to the vCPU state.
<i>caps_reg</i>	Capability register index (see <a href="#">L4_vm_vmx_caps_regs</a> ).

**Returns**

The value of the capability register.

Definition at line 884 of file [\\_\\_vm-vmx.h](#).

References [L4\\_NOTHROW](#).

**l4\_vm\_vmx\_get\_caps\_default1()**

```
l4_uint32_t l4_vm_vmx_get_caps_default1 (
    l4_vm_vmx_vcpu_state_t const * vcpu_state,
    enum L4_vm_vmx_dfl1_regs dfl1_reg) [inline]
```

Get a default to one capability register for VMX.

**Parameters**

<i>vcpu_state</i>	Pointer to the vCPU state.
<i>dfl1_reg</i>	Default to 1 capability register index (see <a href="#">L4_vm_vmx_dfl1_regs</a> ).

**Returns**

The value of the capability register.

Definition at line 892 of file [\\_\\_vm-vmx.h](#).

References [L4\\_NOTHROW](#).

**l4\_vm\_vmx\_get\_cr2\_index()**

```
l4_uint32_t l4_vm_vmx_get_cr2_index (
    l4_vm_vmx_vcpu_vmcs_t const * vmcs) [inline]
```

Get the software VMCS field index of the virtual CR2 register.

**Parameters**

<i>vmcs</i>	Pointer to the software VMCS.
-------------	-------------------------------

**Returns**

The field index used for the virtual CR2 register as used by the current Fiasco.OC interface.

The CR2 register is actually not in the hardware VMCS, however our VMMs run in user mode and need to have access to this register so we put it into our software VMCS.

**See also**

[L4\\_VM\\_VMX\\_VMCS\\_CR2](#)

Definition at line 900 of file [\\_\\_vm-vmx.h](#).

References [L4\\_NOTHROW](#).

**l4\_vm\_vmx\_get\_hw\_vmcs()**

```
l4_cap_idx_t l4_vm_vmx_get_hw_vmcs (
    l4_vm_vmx_vcpu_vmcs_t * vmcs) [inline]
```

Get the vCPU context (i.e.

the hardware VMCS object) associated with the software VMCS.

**Parameters**

<i>vmcs</i>	Pointer to the software VMCS.
-------------	-------------------------------

**Returns**


vCPU context (hardware VMCS object) capability.

Definition at line 915 of file [\\_\\_vm-vmx.h](#).

References [L4\\_CAP\\_MASK](#), and [L4\\_NOTHROW](#).

Referenced by [l4\\_vm\\_vmx\\_clear\(\)](#), and [l4\\_vm\\_vmx\\_ptr\\_load\(\)](#).

Here is the caller graph for this function:

**l4\_vm\_vmx\_ptr\_load()**

```
void l4_vm_vmx_ptr_load (
    l4_vm_vmx_vcpu_vmcs_t * vmcs,
    l4_vm_vmx_vcpu_vmcs_t * src_vmcs) [inline]
```

Load the content from a different software VMCS to the software VMCS.

**Parameters**


<i>vmcs</i>	Pointer to the destination software VMCS.
<i>src_vmcs</i>	Pointer to the source software VMCS.

This function is comparable to the VMX VMPTRLD instruction.

Definition at line 719 of file [\\_\\_vm-vmx.h](#).

References [L4\\_NOTHROW](#), [l4\\_vm\\_vmx\\_clear\(\)](#), [l4\\_vm\\_vmx\\_get\\_hw\\_vmcs\(\)](#), [l4\\_vm\\_vmx\\_set\\_hw\\_vmcs\(\)](#), and [L4\\_VM\\_VMX\\_VMCS\\_SIZE\\_DIRTY\\_BITMAP](#).

Here is the call graph for this function:



### **`l4_vm_vmx_read()`**

```

l4_uint64_t l4_vm_vmx_read (
    l4_vm_vmx_vcpu_vmcs_t * vmcs,
    unsigned field) [inline]
  
```

Read any software VMCS field.

#### **Parameters**

<i>vmcs</i>	Pointer to the software VMCS.
<i>field</i>	The VMCS field index as used on VMX hardware.


#### **Returns**

The value of the software VMCS field with the given index.

Definition at line 787 of file [\\_\\_vm-vmx.h](#).

References [L4\\_NOTHROW](#), [l4\\_vm\\_vmx\\_read\\_16\(\)](#), [l4\\_vm\\_vmx\\_read\\_32\(\)](#), [l4\\_vm\\_vmx\\_read\\_64\(\)](#), and [l4\\_vm\\_vmx\\_read\\_nat\(\)](#).

Here is the call graph for this function:





## **l4\_vm\_vmx\_read\_16()**

```
l4_uint16_t l4_vm_vmx_read_16 (  
    l4_vm_vmx_vcpu_vmcs_t * vmcs,  
    unsigned field) [inline]
```

Read a 16-bit software VMCS field.

### **Parameters**

<i>vmcs</i>	Pointer to the software VMCS.
<i>field</i>	The VMCS field index as used on VMX hardware.

### **Returns**


The value of the software VMCS field with the given index.

Definition at line 754 of file [\\_\\_vm-vmx.h](#).

References [L4\\_NOTHROW](#).

Referenced by [l4\\_vm\\_vmx\\_read\(\)](#).

Here is the caller graph for this function:



## **l4\_vm\_vmx\_read\_32()**

```
l4_uint32_t l4_vm_vmx_read_32 (  
    l4_vm_vmx_vcpu_vmcs_t * vmcs,  
    unsigned field) [inline]
```

Read a 32-bit software VMCS field.

### **Parameters**

<i>vmcs</i>	Pointer to the software VMCS.
<i>field</i>	The VMCS field index as used on VMX hardware.

### Returns


The value of the software VMCS field with the given index.

Definition at line 765 of file [\\_\\_vm-vmx.h](#).

References [L4\\_NOTHROW](#).

Referenced by [l4\\_vm\\_vmx\\_read\(\)](#).

Here is the caller graph for this function:



### **`l4_vm_vmx_read_64()`**

```
l4_uint64_t l4_vm_vmx_read_64 (  
    l4_vm_vmx_vcpu_vmcs_t * vmcs,  
    unsigned field) [inline]
```

Read a 64-bit software VMCS field.

### Parameters

<i>vmcs</i>	Pointer to the software VMCS.
<i>field</i>	The VMCS field index as used on VMX hardware.

### Returns

The value of the software VMCS field with the given index.

Definition at line 776 of file [\\_\\_vm-vmx.h](#).

References [L4\\_NOTHROW](#).

Referenced by [l4\\_vm\\_vmx\\_read\(\)](#).

Here is the caller graph for this function:



## **l4\_vm\_vmx\_read\_nat()**

```
l4_umword_t l4_vm_vmx_read_nat (
    l4_vm_vmx_vcpu_vmcs_t * vmcs,
    unsigned field) [inline]
```

Read a natural-width software VMCS field.

### **Parameters**

<i>vmcs</i>	Pointer to the software VMCS.
<i>field</i>	The VMCS field index as used on VMX hardware.

### **Returns**

The value of the software VMCS field with the given index.

Definition at line 743 of file [\\_\\_vm-vmx.h](#).

References [L4\\_NOTHROW](#).

Referenced by [l4\\_vm\\_vmx\\_read\(\)](#).

Here is the caller graph for this function:



## **l4\_vm\_vmx\_set\_hw\_vmcs()**

```
void l4_vm_vmx_set_hw_vmcs (
    l4_vm_vmx_vcpu_vmcs_t * vmcs,
    l4_cap_idx_t vmcs_cap) [inline]
```

Associate the software VMCS with a vCPU context, i.e.

a hardware VMCS object.

The VMX extended vCPU state is unable to be resumed unless it is associated with a vCPU context, i.e. a hardware VMCS object: An `L4::Vcpu_context` from the user space point of view with its kernel counterpart `Vmx_vmcs`.

**Note**

When replacing the vCPU context, the dirty bitmap of the software VMCS is not touched, neither by the kernel nor by the API functions. This is on purpose, to enable efficient switching between separate VMs in the common case. If there is a logical discrepancy between the content of the software VMCS and the replaced vCPU context, the user is responsible for explicitly setting the relevant software VMCS fields and/or the relevant software VMCS dirty bitmap bits to ensure that the discrepancy is rectified on the next vCPU resume. This needs to be done regardless of using the API functions (the preferred way) or accessing the data structures directly (the discouraged way).

Replacing the vCPU context while the vCPU is currently running has no immediate effect until the next vCPU resume. In addition to that, the kernel might cache the vCPU context internally (in other words, the capability is not looked up on every vCPU resume). To remove the association of the current vCPU context, simply replace it by an another vCPU context. The reference count of the previous vCPU context will be decremented accordingly on the next vCPU resume.

To remove the association of the current vCPU context without replacing it by an another vCPU context, pass an invalid capability with the bit 3 set and trigger a vCPU resume. The vCPU resume will fail in this case (due to the missing vCPU context), but the reference count of the previous vCPU context will be decremented accordingly.

There is no need to explicitly remove the association of the current vCPU context before deleting the software VMCS. Deleting the software VMCS automatically disassociates it from the vCPU context and a vCPU context with a reference count of 0 will be eventually deleted as well.

If the hardware limitations on the usage of the vCPU context are not observed (i.e. no hardware VMCS being active on more than one physical CPU), the vCPU will fail to resume.

**Parameters**


<i>vmcs</i>	Pointer to the software VMCS.
<i>vmcs_cap</i>	vCPU context (hardware VMCS object) capability.

Definition at line 907 of file [\\_\\_vm-vmx.h](#).

References [L4\\_NOTHROW](#).

Referenced by [l4\\_vm\\_vmx\\_clear\(\)](#), and [l4\\_vm\\_vmx\\_ptr\\_load\(\)](#).

Here is the caller graph for this function:

**`l4_vm_vmx_write()`**

```

void l4_vm_vmx_write (
    l4_vm_vmx_vcpu_vmcs_t * vmcs,
    unsigned field,
    l4_uint64_t val) [inline]

```

Write to an arbitrary software VMCS field.


#### Parameters

<i>vmcs</i>	Pointer to the software VMCS.
<i>field</i>	The VMCS field index as used on VMX hardware.
<i>val</i>	The value that shall be written to the given field.

Definition at line 868 of file [\\_\\_vm-vmx.h](#).

References [L4\\_NOTHROW](#), [l4\\_vm\\_vmx\\_write\\_16\(\)](#), [l4\\_vm\\_vmx\\_write\\_32\(\)](#), [l4\\_vm\\_vmx\\_write\\_64\(\)](#), and [l4\\_vm\\_vmx\\_write\\_nat\(\)](#).

Here is the call graph for this function:



#### `l4_vm_vmx_write_16()`

```
void l4_vm_vmx_write_16 (  
    l4_vm_vmx_vcpu_vmcs_t * vmcs,  
    unsigned field,  
    l4_uint16_t val) [inline]
```

Write to a 16-bit software VMCS field.

#### Parameters


<i>vmcs</i>	Pointer to the software VMCS.
<i>field</i>	The VMCS field index as used on VMX hardware.
<i>val</i>	The value that shall be written to the given field.

Definition at line 820 of file [\\_\\_vm-vmx.h](#).

References [L4\\_NOTHROW](#).

Referenced by [l4\\_vm\\_vmx\\_write\(\)](#).

Here is the caller graph for this function:



### **l4\_vm\_vmx\_write\_32()**

```
void l4_vm_vmx_write_32 (  
    l4_vm_vmx_vcpu_vmcs_t * vmcs,  
    unsigned field,  
    l4_uint32_t val) [inline]
```

Write to a 32-bit software VMCS field.

#### **Parameters**

<i>vmcs</i>	Pointer to the software VMCS.
<i>field</i>	The VMCS field index as used on VMX hardware.
<i>val</i>	The value that shall be written to the given field.

Definition at line [836](#) of file [\\_\\_vm-vmx.h](#).

References [L4\\_NOTHROW](#).

Referenced by [l4\\_vm\\_vmx\\_write\(\)](#).

Here is the caller graph for this function:



**l4\_vm\_vmx\_write\_64()**

```
void l4_vm_vmx_write_64 (  
    l4_vm_vmx_vcpu_vmcs_t * vmcs,  
    unsigned field,  
    l4_uint64_t val) [inline]
```

Write to a 64-bit software VMCS field.

**Parameters**


<i>vmcs</i>	Pointer to the software VMCS.
<i>field</i>	The VMCS field index as used on VMX hardware.
<i>val</i>	The value that shall be written to the given field.

Definition at line 852 of file [\\_\\_vm-vmx.h](#).

References [L4\\_NOTHROW](#).

Referenced by [l4\\_vm\\_vmx\\_write\(\)](#).

Here is the caller graph for this function:

**l4\_vm\_vmx\_write\_nat()**

```
void l4_vm_vmx_write_nat (  
    l4_vm_vmx_vcpu_vmcs_t * vmcs,  
    unsigned field,  
    l4_umword_t val) [inline]
```

Write to a natural-width software VMCS field.

**Parameters**


<i>vmcs</i>	Pointer to the software VMCS.
<i>field</i>	The VMCS field index as used on VMX hardware.
<i>val</i>	The value that shall be written to the given field.

Definition at line 804 of file [\\_\\_vm-vmx.h](#).

References [L4\\_NOTHROW](#).

Referenced by [l4\\_vm\\_vmx\\_write\(\)](#).


Here is the caller graph for this function:



#### 13.1.10.6.4 VM API for TZ

Virtual Machine API for ARM TrustZone.

Collaboration diagram for VM API for TZ:



#### Data Structures

- struct [l4\\_vm\\_tz\\_state](#)  
*state structure for TrustZone VMs*


##### 13.1.10.6.4.1 Detailed Description

Virtual Machine API for ARM TrustZone.

#### 13.1.10.7 Interrupt controller

The C lcu interface, see [L4::lcu](#) for the C++ interface.

Collaboration diagram for Interrupt controller:





## Data Structures

- struct [l4\\_icu\\_info\\_t](#)  
*Info structure for an ICU.*

## Typedefs

- typedef struct [l4\\_icu\\_info\\_t](#) [l4\\_icu\\_info\\_t](#)  
*Info structure for an ICU.*

## Enumerations

- enum [L4\\_icu\\_flags](#) { [L4\\_ICU\\_FLAG\\_MSI](#) }  
*Flags for IRQ numbers used for the ICU.*

## Functions

- [l4\\_msgtag\\_t](#) [l4\\_icu\\_bind](#) ([l4\\_cap\\_idx\\_t](#) icu, unsigned irqnum, [l4\\_cap\\_idx\\_t](#) irq) [L4\\_NOTHROW](#)  
*Bind an interrupt line of an interrupt controller to an interrupt object.*
- [l4\\_msgtag\\_t](#) [l4\\_icu\\_bind\\_u](#) ([l4\\_cap\\_idx\\_t](#) icu, unsigned irqnum, [l4\\_cap\\_idx\\_t](#) irq, [l4\\_utcb\\_t](#) \*utcb) [L4\\_NOTHROW](#)  
*Bind an interrupt line of an interrupt controller to an interrupt object.*
- [l4\\_msgtag\\_t](#) [l4\\_icu\\_unbind](#) ([l4\\_cap\\_idx\\_t](#) icu, unsigned irqnum, [l4\\_cap\\_idx\\_t](#) irq) [L4\\_NOTHROW](#)  
*Remove binding of an interrupt line from the interrupt controller object.*
- [l4\\_msgtag\\_t](#) [l4\\_icu\\_unbind\\_u](#) ([l4\\_cap\\_idx\\_t](#) icu, unsigned irqnum, [l4\\_cap\\_idx\\_t](#) irq, [l4\\_utcb\\_t](#) \*utcb) [L4\\_NOTHROW](#)  
*Remove binding of an interrupt line from the interrupt controller object.*
- [l4\\_msgtag\\_t](#) [l4\\_icu\\_set\\_mode](#) ([l4\\_cap\\_idx\\_t](#) icu, unsigned irqnum, [l4\\_umword\\_t](#) mode) [L4\\_NOTHROW](#)  
*Set interrupt mode.*
- [l4\\_msgtag\\_t](#) [l4\\_icu\\_set\\_mode\\_u](#) ([l4\\_cap\\_idx\\_t](#) icu, unsigned irqnum, [l4\\_umword\\_t](#) mode, [l4\\_utcb\\_t](#) \*utcb) [L4\\_NOTHROW](#)  
*Set interrupt mode.*
- [l4\\_msgtag\\_t](#) [l4\\_icu\\_info](#) ([l4\\_cap\\_idx\\_t](#) icu, [l4\\_icu\\_info\\_t](#) \*info) [L4\\_NOTHROW](#)  
*Get information about the ICU features.*
- [l4\\_msgtag\\_t](#) [l4\\_icu\\_info\\_u](#) ([l4\\_cap\\_idx\\_t](#) icu, [l4\\_icu\\_info\\_t](#) \*info, [l4\\_utcb\\_t](#) \*utcb) [L4\\_NOTHROW](#)  
*Get information about the ICU features.*
- [l4\\_msgtag\\_t](#) [l4\\_icu\\_msi\\_info](#) ([l4\\_cap\\_idx\\_t](#) icu, unsigned irqnum, [l4\\_uint64\\_t](#) source, [l4\\_icu\\_msi\\_info\\_t](#) \*msi\_info) [L4\\_NOTHROW](#)  
*Get MSI info about IRQ.*
- [l4\\_msgtag\\_t](#) [l4\\_icu\\_msi\\_info\\_u](#) ([l4\\_cap\\_idx\\_t](#) icu, unsigned irqnum, [l4\\_uint64\\_t](#) source, [l4\\_icu\\_msi\\_info\\_t](#) \*msi\_info, [l4\\_utcb\\_t](#) \*utcb) [L4\\_NOTHROW](#)  
*Get MSI info about IRQ.*
- [l4\\_msgtag\\_t](#) [l4\\_icu\\_unmask](#) ([l4\\_cap\\_idx\\_t](#) icu, unsigned irqnum, [l4\\_umword\\_t](#) \*label, [l4\\_timeout\\_t](#) to) [L4\\_NOTHROW](#)  
*Unmask an IRQ line.*
- [l4\\_msgtag\\_t](#) [l4\\_icu\\_unmask\\_u](#) ([l4\\_cap\\_idx\\_t](#) icu, unsigned irqnum, [l4\\_umword\\_t](#) \*label, [l4\\_timeout\\_t](#) to, [l4\\_utcb\\_t](#) \*utcb) [L4\\_NOTHROW](#)  
*Unmask the given interrupt line.*
- [l4\\_msgtag\\_t](#) [l4\\_icu\\_mask](#) ([l4\\_cap\\_idx\\_t](#) icu, unsigned irqnum, [l4\\_umword\\_t](#) \*label, [l4\\_timeout\\_t](#) to) [L4\\_NOTHROW](#)  
*Mask an IRQ line.*
- [l4\\_msgtag\\_t](#) [l4\\_icu\\_mask\\_u](#) ([l4\\_cap\\_idx\\_t](#) icu, unsigned irqnum, [l4\\_umword\\_t](#) \*label, [l4\\_timeout\\_t](#) to, [l4\\_utcb\\_t](#) \*utcb) [L4\\_NOTHROW](#)  
*Mask an IRQ line.*

### 13.1.10.7.1 Detailed Description

The C Icu interface, see [L4::Icu](#) for the C++ interface.

#### Note

"ICU" is short for "interrupt control unit".

These functions define the interface for interrupt controllers, for binding IRQ objects to interrupt lines and other interrupt sources, as well as functions for masking and unmasking of interrupts.

To setup an IRQ line the following steps are required:

1. [l4\\_icu\\_set\\_mode\(\)](#) (optional if IRQ has a default mode)
2. [l4\\_rcv\\_ep\\_bind\\_thread\(\)](#) or [l4\\_rcv\\_ep\\_bind\\_snd\\_destination\(\)](#) to attach the IRQ object to a thread object.
3. [l4\\_icu\\_bind\(\)](#)
4. [l4\\_icu\\_unmask\(\)](#) to receive the first IRQ

For certain interrupt sources only some of these steps are necessary and supported, see [Scheduler](#) and [Virtual Console](#).

At most one [IRQs](#) object can be bound to a certain interrupt source and a certain [IRQs](#) object can be bound to at most one interrupt source.

#### Include File

```
#include <l4/sys/icu.h>
```

### 13.1.10.7.2 Typedef Documentation

#### 13.1.10.7.2.1 l4\_icu\_info\_t

```
typedef struct l4_icu_info_t l4_icu_info_t
```

Info structure for an ICU.

This structure contains information about the features of an ICU.

#### See also

[l4\\_icu\\_info\(\)](#).

### 13.1.10.7.3 Enumeration Type Documentation

#### 13.1.10.7.3.1 L4\_icu\_flags

enum [L4\\_icu\\_flags](#)

Flags for IRQ numbers used for the ICU.

##### Enumerator

<a href="#">L4_ICU_FLAG_MSI</a>	Flag to denote that the IRQ is actually an MSI. This flag may be used for <a href="#">l4_icu_bind()</a> and <a href="#">l4_icu_unbind()</a> functions to denote that the IRQ number is meant to be an MSI.
---------------------------------	--

Definition at line 53 of file [icu.h](#).

### 13.1.10.7.4 Function Documentation

#### 13.1.10.7.4.1 l4\_icu\_bind()

```
l4\_msgtag\_t l4_icu_bind (
    l4\_cap\_idx\_t icu,
    unsigned irqnum,
    l4\_cap\_idx\_t irq) [inline]
```

Bind an interrupt line of an interrupt controller to an interrupt object.

##### Parameters

<i>icu</i>	ICU object to bind <i>irq</i> to.
<i>irqnum</i>	IRQ line at the ICU.
<i>irq</i>	IRQ object to bind to this ICU.

##### Returns

Syscall return tag. The caller should check the return value using [l4\\_error\(\)](#) to check for errors and to identify the correct method for unmasking the interrupt. Return values < 0 indicate an error. A return value of 0 means a direct unmask via the IRQ object using [l4\\_irq\\_unmask\(\)](#). A return value of 1 means that the interrupt has to be unmasked via the ICU using [l4\\_icu\\_unmask\(\)](#).

##### Return values

<a href="#">-L4_EINVAL</a>	<i>irq</i> is bound to an interrupt source.
<a href="#">-L4_EPERM</a>	Insufficient permissions; see precondition.

**Precondition**

The capability `irq` must have the permission [L4\\_CAP\\_FPAGE\\_W](#).

In case the `irq` is already bound to an interrupt source, it is unbound first. In case the `irq` is bound and the interrupt source is bound to a different IRQ object, only the unbinding happens. An IRQ object that is bound to an interrupt source will get unbound if the IRQ object is deleted.


**Examples**

[examples/sys/isr/main.c](#).

Definition at line 496 of file [icu.h](#).

References [l4\\_icu\\_bind\\_u\(\)](#), [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:

**13.1.10.7.4.2 l4\_icu\_bind\_u()**

```

l4_msgtag_t l4_icu_bind_u (
    l4_cap_idx_t icu,
    unsigned irqnum,
    l4_cap_idx_t irq,
    l4_utcb_t * utcb) [inline]

```

Bind an interrupt line of an interrupt controller to an interrupt object.

**Parameters**

<i>icu</i>	The ICU object to bind <code>irq</code> to.
<i>irqnum</i>	IRQ line at the ICU.
<i>irq</i>	IRQ object for the given IRQ line to bind to this ICU.
<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. See <a href="#">l4_utcb</a> .

## Returns

Syscall return tag. The caller should check the return value using [l4\\_error\(\)](#) to check for errors and to identify the correct method for unmasking the interrupt. Return values  $< 0$  indicate an error. A return value of 0 means a direct unmask via the IRQ object using [L4::irq::unmask](#). A return value of 1 means that the interrupt has to be unmasked via the ICU using [L4::icu::unmask](#).

## Return values

<a href="#">-L4_EINVAL</a>	<code>irq</code> is bound to an interrupt source.
<a href="#">-L4_EPERM</a>	Insufficient permissions; see precondition.

## Precondition

The capability `irq` must have the permission [L4\\_CAP\\_FPAGE\\_W](#).


In case the `irq` is already bound to an interrupt source, it is unbound first. In case the `irq` is bound and the interrupt source is bound to a different [L4::irq](#) object, only the unbinding happens. An [L4::irq](#) object that is bound to an interrupt source will get unbound if the [L4::irq](#) object is deleted.

Definition at line 396 of file [icu.h](#).


References [L4\\_CAP\\_FPAGE\\_RWS](#), [L4\\_ICU\\_OP\\_BIND](#), [l4\\_ipc\\_call\(\)](#), [L4\\_IPC\\_NEVER](#), [l4\\_map\\_obj\\_control\(\)](#), [l4\\_msgtag\(\)](#), [L4\\_NOTHROW](#), [l4\\_obj\\_fpage\(\)](#), [L4\\_PROTO\\_IRQ](#), [l4\\_msg\\_regs\\_t::mr](#), and [l4\\_fpage\\_t::raw](#).

Referenced by [L4::icu::bind\(\)](#), and [l4\\_icu\\_bind\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



#### 13.1.10.7.4.3 l4\_icu\_info()

```
l4_msgtag_t l4_icu_info (
    l4_cap_idx_t icu,
    l4_icu_info_t * info) [inline]
```

Get information about the ICU features.

##### Parameters

	<i>icu</i>	The ICU object from which information shall be retrieved.
out	<i>info</i>	Info structure to be filled with information.


##### Returns

Syscall return tag

Definition at line 504 of file [icu.h](#).

References [l4\\_icu\\_info\\_u\(\)](#), [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:



#### 13.1.10.7.4.4 l4\_icu\_info\_u()

```
l4_msgtag_t l4_icu_info_u (
    l4_cap_idx_t icu,
    l4_icu_info_t * info,
    l4_utcb_t * utcb) [inline]
```

Get information about the ICU features.

##### Parameters

	<i>icu</i>	The ICU object from which MSI information shall be retrieved.
out	<i>info</i>	Info structure to be filled with information.
	<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. See <a href="#">l4_utcb</a> .

**Returns**


Syscall return tag

Definition at line 420 of file [icu.h](#).


References [L4\\_ICU\\_OP\\_INFO](#), [l4\\_ipc\\_call\(\)](#), [L4\\_IPC\\_NEVER](#), [l4\\_msgtag\(\)](#), [L4\\_NOTHROW](#), [L4\\_PROTO\\_IRQ](#), and [l4\\_msg\\_regs\\_t::mr](#).

Referenced by [L4::Icu::info\(\)](#), and [l4\\_icu\\_info\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:

**13.1.10.7.4.5 l4\_icu\_mask()**

```

l4_msgtag_t l4_icu_mask (
    l4_cap_idx_t icu,
    unsigned irqnum,
    l4_umword_t * label,
    l4_timeout_t to) [inline]
  
```

Mask an IRQ line.

**Parameters**

<i>icu</i>	The ICU object where the IRQ line shall be masked.
------------	--

<i>irqnum</i>	IRQ line at the ICU.
<i>label</i>	If non-NULL, the function also performs an open wait IPC operation waiting for the next message, and the received label is returned here.
<i>to</i>	IPC timeout, if unsure use L4_IPC_NEVER.

#### Returns

Syscall return tag. If *label* is NULL, this function performs an IPC send-only operation and there is no return value except [L4\\_MSGTAG\\_ERROR](#) indicating success or failure of the send operation. In this case use [l4\\_ipc\\_error\(\)](#) to check for errors and **do not** use [l4\\_error\(\)](#).

Definition at line 518 of file [icu.h](#).

References [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:



#### 13.1.10.7.4.6 l4\_icu\_mask\_u()

```

l4_msgtag_t l4_icu_mask_u (
    l4_cap_idx_t icu,
    unsigned irqnum,
    l4_umword_t * label,
    l4_timeout_t to,
    l4_utcb_t * utcb) [inline]
  
```

Mask an IRQ line.

#### Parameters

<i>icu</i>	The ICU object where the IRQ line shall be masked.
<i>irqnum</i>	IRQ line at the ICU.
<i>label</i>	If NULL, this function is a send-only message to the ICU. If not NULL, this function will enter an open wait after sending the mask message and the received label is returned here.
<i>to</i>	The timeout-pair (send and receive) that shall be used for this operation. The receive timeout is used with a non-NULL <i>label</i> only.
<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. See <a href="#">l4_utcb</a> .



**Returns**

Syscall return tag. If `label` is `NULL`, this function performs an IPC send-only operation and there is no return value except `L4_MSGTAG_ERROR` indicating success or failure of the send operation. In this case use `l4_ipc_error()` to check for errors and **do not** use `l4_error()`.

Definition at line 483 of file `icu.h`.

References `L4_NOTHROW`.

Referenced by `L4::Icu::mask()`.

Here is the caller graph for this function:

**13.1.10.7.4.7 l4\_icu\_msi\_info()**

```

l4_msgtag_t l4_icu_msi_info (
    l4_cap_idx_t icu,
    unsigned irqnum,
    l4_uint64_t source,
    l4_icu_msi_info_t * msi_info) [inline]
  
```

Get MSI info about IRQ.

**Parameters**

	<i>icu</i>	The ICU object from which MSI information shall be retrieved.
	<i>irqnum</i>	IRQ line at the ICU.
	<i>source</i>	Platform dependent requester ID for MSIs. On IA32 we use a 20bit source filter value as described in the Intel IRQ remapping specification.
out	<i>msi_info</i>	A <code>l4_icu_msi_info_t</code> structure receiving the address and the data value to trigger this MSI.


**Returns**

Syscall return tag

Definition at line 508 of file `icu.h`.

References `l4_icu_msi_info_u()`, `L4_NOTHROW`, and `l4_utcb()`.

Here is the call graph for this function:



#### 13.1.10.7.4.8 l4\_icu\_msi\_info\_u()

```

l4_msgtag_t l4_icu_msi_info_u (
    l4_cap_idx_t icu,
    unsigned irqnum,
    l4_uint64_t source,
    l4_icu_msi_info_t * msi_info,
    l4_utcb_t * utcb) [inline]
  
```

Get MSI info about IRQ.

#### Parameters

	<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. See <a href="#">l4_utcb</a> .
	<i>icu</i>	The ICU object from which MSI information shall be retrieved.
	<i>irqnum</i>	IRQ line at the ICU.
	<i>source</i>	Platform dependent requester ID for MSIs. On IA32 we use a 20bit source filter value as described in the Intel IRQ remapping specification.
out	<i>msi_info</i>	A <a href="#">l4_icu_msi_info_t</a> structure receiving the address and the data value to trigger this MSI.

#### Returns


Syscall return tag

Definition at line 434 of file [icu.h](#).

References [L4\\_ICU\\_OP\\_MSI\\_INFO](#), [l4\\_ipc\\_call\(\)](#), [L4\\_IPC\\_NEVER](#), [l4\\_msgtag\(\)](#), [l4\\_msgtag\\_has\\_error\(\)](#), [l4\\_msgtag\\_words\(\)](#), [L4\\_NOTHROW](#), [L4\\_PROTO\\_IRQ](#), [L4\\_UNLIKELY](#), [l4\\_utcb\\_mr64\\_idx\(\)](#), [l4\\_msg\\_regs\\_t::mr](#), and [l4\\_msg\\_regs\\_t::mr64](#).

Referenced by [l4\\_icu\\_msi\\_info\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



#### 13.1.10.7.4.9 l4\_icu\_set\_mode()

```

l4_msgtag_t l4_icu_set_mode (
    l4_cap_idx_t icu,
    unsigned irqnum,
    l4_umword_t mode) [inline]
  
```

Set interrupt mode.

#### Parameters

<i>icu</i>	The ICU object.
<i>irqnum</i>	IRQ line at the ICU.
<i>mode</i>	Mode, see <a href="#">L4_irq_mode</a> .


**Returns**

Syscall return tag

Definition at line 523 of file [icu.h](#).

References [l4\\_icu\\_set\\_mode\\_u\(\)](#), [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:

**13.1.10.7.4.10 l4\_icu\_set\_mode\_u()**

```

l4_msgtag_t l4_icu_set_mode_u (
    l4_cap_idx_t icu,
    unsigned irqnum,
    l4_umword_t mode,
    l4_utcb_t * utcb) [inline]
  
```

Set interrupt mode.

**Parameters**

<i>icu</i>	The ICU object.
<i>irqnum</i>	IRQ line at the ICU.
<i>mode</i>	Mode, see <a href="#">L4_irq_mode</a> .
<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. See <a href="#">l4_utcb</a> .

**Returns**


Syscall return tag

Definition at line 457 of file [icu.h](#).


References [L4\\_ICU\\_OP\\_SET\\_MODE](#), [l4\\_ipc\\_call\(\)](#), [L4\\_IPC\\_NEVER](#), [l4\\_msgtag\(\)](#), [L4\\_NOTHROW](#), [L4\\_PROTO\\_IRQ](#), and [l4\\_msg\\_regs\\_t::mr](#).

Referenced by [l4\\_icu\\_set\\_mode\(\)](#), and [L4::l4u::set\\_mode\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



#### 13.1.10.7.4.11 l4\_icu\_unbind()

```

l4_msgtag_t l4_icu_unbind (
    l4_cap_idx_t icu,
    unsigned irqnum,
    l4_cap_idx_t irq) [inline]
  
```

Remove binding of an interrupt line from the interrupt controller object.

##### Parameters

<i>icu</i>	The ICU object from where the binding shall be removed.
<i>irqnum</i>	IRQ line at the ICU.
<i>irq</i>	IRQ object to remove from the ICU.


**Returns**

Syscall return tag

Definition at line 500 of file [icu.h](#).

References [l4\\_icu\\_unbind\\_u\(\)](#), [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:

**13.1.10.7.4.12 l4\_icu\_unbind\_u()**

```

l4_msgtag_t l4_icu_unbind_u (
    l4_cap_idx_t icu,
    unsigned irqnum,
    l4_cap_idx_t irq,
    l4_utcb_t * utcb) [inline]
  
```

Remove binding of an interrupt line from the interrupt controller object.

**Parameters**

<i>icu</i>	The ICU object from where the binding shall be removed.
<i>irqnum</i>	IRQ line at the ICU.
<i>irq</i>	IRQ object to remove from the ICU.
<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. See <a href="#">l4_utcb</a> .

**Returns**


Syscall return tag

Definition at line 408 of file [icu.h](#).


References [L4\\_CAP\\_FPAGE\\_RWS](#), [L4\\_ICU\\_OP\\_UNBIND](#), [l4\\_ipc\\_call\(\)](#), [L4\\_IPC\\_NEVER](#), [l4\\_map\\_obj\\_control\(\)](#), [l4\\_msgtag\(\)](#), [L4\\_NOTHROW](#), [l4\\_obj\\_fpage\(\)](#), [L4\\_PROTO\\_IRQ](#), [l4\\_msg\\_regs\\_t::mr](#), and [l4\\_fpage\\_t::raw](#).

Referenced by [l4\\_icu\\_unbind\(\)](#), and [L4::l4u::unbind\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



#### 13.1.10.7.4.13 l4\_icu\_unmask()

```

l4_msgtag_t l4_icu_unmask (
    l4_cap_idx_t icu,
    unsigned irqnum,
    l4_umword_t * label,
    l4_timeout_t to) [inline]
  
```

Unmask an IRQ line.

#### Parameters

<i>icu</i>	The ICU object where the IRQ line shall be unmasked.
<i>irqnum</i>	IRQ line at the ICU.
<i>label</i>	If non-NULL, the function also performs an open wait IPC operation waiting for the next message, and the received label is returned here.
<i>to</i>	IPC timeout, if unsure use <code>L4_IPC_NEVER</code> .

## Returns

Syscall return tag. If `label` is `NULL`, this function performs an IPC send-only operation and there is no return value except `L4_MSGTAG_ERROR` indicating success or failure of the send operation. In this case use `l4_ipc_error()` to check for errors and **do not** use `l4_error()`.

Definition at line 513 of file `icu.h`.

References `L4_NOTHROW`, and `l4_utcb()`.

Here is the call graph for this function:



#### 13.1.10.7.4.14 l4\_icu\_unmask\_u()

```

l4_msgtag_t l4_icu_unmask_u (
    l4_cap_idx_t icu,
    unsigned irqnum,
    l4_umword_t * label,
    l4_timeout_t to,
    l4_utcb_t * utcb) [inline]
  
```

Unmask the given interrupt line.

## Parameters

<i>icu</i>	The ICU object where the IRQ line shall be unmasked. When the object is an IRQ, the given interrupt line is ignored and instead the line which the IRQ is bound to (if any) is unmasked.
------------	--

Its counterpart for explicitly masking an interrupt line is `L4::l4cu::mask()`.

## Parameters

	<i>irqnum</i>	The interrupt line that shall be unmasked. Ignored if the object is an IRQ.
out	<i>label</i>	If <code>NULL</code> , this is a send-only unmask. If not <code>NULL</code> , this operation enters an open wait and the <i>protected label</i> shall be received here.
	<i>to</i>	The timeout-pair (send and receive) that shall be used for this operation. The receive timeout is used with a non- <code>NULL label</code> only.
	<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. See <code>l4_utcb</code> .



## Returns

Syscall return tag. If `label` is `NULL`, this function performs an IPC send-only operation and there is no return value except `L4_MSGTAG_ERROR` indicating success or failure of the send operation. In this case use `l4_ipc_error()` to check for errors and **do not** use `l4_error()`.

Definition at line 488 of file `icu.h`.

References `L4_NOTHROW`.

## 13.1.10.8 IRQs

C IRQ interface, see `L4::Irq` for the C++ interface.

Collaboration diagram for IRQs:



## Enumerations

- enum `L4_irq_mode` {  
`L4_IRQ_F_NONE` = 0 , `L4_IRQ_F_SET_MODE` = 0x1 , `L4_IRQ_F_LEVEL` = 0x2 , `L4_IRQ_F_EDGE` = 0x0 ,  
`L4_IRQ_F_POS` = 0x0 , `L4_IRQ_F_NEG` = 0x4 , `L4_IRQ_F_BOTH` = 0x8 , `L4_IRQ_F_LEVEL_HIGH` =  
`L4_IRQ_F_SET_MODE` | `L4_IRQ_F_LEVEL` | `L4_IRQ_F_POS` ,  
`L4_IRQ_F_LEVEL_LOW` = `L4_IRQ_F_SET_MODE` | `L4_IRQ_F_LEVEL` | `L4_IRQ_F_NEG` , `L4_IRQ_F_POS_EDGE`  
= `L4_IRQ_F_SET_MODE` | `L4_IRQ_F_EDGE` | `L4_IRQ_F_POS` , `L4_IRQ_F_NEG_EDGE` = `L4_IRQ_F_`  
`SET_MODE` | `L4_IRQ_F_EDGE` | `L4_IRQ_F_NEG` , `L4_IRQ_F_BOTH_EDGE` = `L4_IRQ_F_SET_MODE` |  
`L4_IRQ_F_EDGE` | `L4_IRQ_F_BOTH` ,  
`L4_IRQ_F_MASK` = 0xf , `L4_IRQ_F_SET_WAKEUP` = 0x10 , `L4_IRQ_F_CLEAR_WAKEUP` = 0x20 }

*Interrupt attributes.*

## Functions

- `l4_msgtag_t l4_irq_detach (l4_cap_idx_t irq) L4_NOTHROW`  
*Detach from an interrupt source.*
- `l4_msgtag_t l4_irq_detach_u (l4_cap_idx_t irq, l4_utcb_t *utcb) L4_NOTHROW`  
*Detach from this interrupt.*
- `l4_msgtag_t l4_irq_bind_vcpu (l4_cap_idx_t irq, l4_cap_idx_t thread, l4_umword_t cfg) L4_NOTHROW`  
*Bind a thread to this Irq for vCPU interrupt forwarding.*
- `l4_msgtag_t l4_irq_bind_vcpu_u (l4_cap_idx_t irq, l4_cap_idx_t thread, l4_umword_t cfg, l4_utcb_t *utcb) L4_NOTHROW`  
*Bind a thread to this Irq for vCPU interrupt forwarding.*
- `l4_msgtag_t l4_irq_trigger (l4_cap_idx_t irq) L4_NOTHROW`  
*Trigger an IRQ.*

- [l4\\_msgtag\\_t l4\\_irq\\_trigger\\_u](#) ([l4\\_cap\\_idx\\_t](#) irq, [l4\\_utcb\\_t](#) \*utcb) [L4\\_NOTHROW](#)  
*Trigger the object.*
- [l4\\_msgtag\\_t l4\\_irq\\_receive](#) ([l4\\_cap\\_idx\\_t](#) irq, [l4\\_timeout\\_t](#) to) [L4\\_NOTHROW](#)  
*Unmask and wait for specified IRQ.*
- [l4\\_msgtag\\_t l4\\_irq\\_receive\\_u](#) ([l4\\_cap\\_idx\\_t](#) irq, [l4\\_timeout\\_t](#) timeout, [l4\\_utcb\\_t](#) \*utcb) [L4\\_NOTHROW](#)  
*Unmask and wait for this IRQ.*
- [l4\\_msgtag\\_t l4\\_irq\\_wait](#) ([l4\\_cap\\_idx\\_t](#) irq, [l4\\_umword\\_t](#) \*label, [l4\\_timeout\\_t](#) to) [L4\\_NOTHROW](#)  
*Unmask IRQ and wait for any message.*
- [l4\\_msgtag\\_t l4\\_irq\\_wait\\_u](#) ([l4\\_cap\\_idx\\_t](#) irq, [l4\\_umword\\_t](#) \*label, [l4\\_timeout\\_t](#) timeout, [l4\\_utcb\\_t](#) \*utcb) [L4\\_NOTHROW](#)  
*Unmask IRQ and (open) wait for any message.*
- [l4\\_msgtag\\_t l4\\_irq\\_unmask](#) ([l4\\_cap\\_idx\\_t](#) irq) [L4\\_NOTHROW](#)  
*Unmask IRQ.*
- [l4\\_msgtag\\_t l4\\_irq\\_unmask\\_u](#) ([l4\\_cap\\_idx\\_t](#) irq, [l4\\_utcb\\_t](#) \*utcb) [L4\\_NOTHROW](#)  
*Unmask this IRQ.*

### 13.1.10.8.1 Detailed Description

C IRQ interface, see [L4::Irq](#) for the C++ interface.

The IRQ interface provides access to abstract interrupts provided by the microkernel. Interrupts may be

- hardware interrupts provided by the platform interrupt controller,
- virtual device interrupts provided by the microkernel's virtual devices (virtual serial or trace buffer) or
- virtual interrupts that can be triggered by user programs (IRQs) via [l4\\_irq\\_trigger\(\)](#).

For hardware and virtual device interrupts the `Irq` object must be bound to an interrupt source, see [Interrupt controller](#). To receive interrupts, the `Irq` object must be bound to a thread, see [l4\\_rcv\\_ep\\_bind\\_thread\(\)](#) and [l4\\_rcv\\_ep\\_bind\\_snd\\_destination\(\)](#).

IRQ objects can be created using a factory, see the [Factory](#) API (use [l4\\_factory\\_create\\_irq\(\)](#)).

#### Include File

```
#include <l4/sys/irq.h>
```

For the C++ interface refer to the [L4::Irq](#) API for an overview.

### 13.1.10.8.2 Enumeration Type Documentation

#### 13.1.10.8.2.1 L4\_irq\_mode

enum `L4_irq_mode`

Interrupt attributes.

##### Enumerator

<code>L4_IRQ_F_NONE</code>	Flow types. None
<code>L4_IRQ_F_SET_MODE</code>	Valid flag, if not set, the <code>set_mode</code> operation does nothing.
<code>L4_IRQ_F_LEVEL</code>	Level triggered.
<code>L4_IRQ_F_EDGE</code>	Edge triggered.
<code>L4_IRQ_F_POS</code>	Positive trigger.
<code>L4_IRQ_F_NEG</code>	Negative trigger.
<code>L4_IRQ_F_BOTH</code>	Both edges trigger.
<code>L4_IRQ_F_LEVEL_HIGH</code>	Level high trigger.
<code>L4_IRQ_F_LEVEL_LOW</code>	Level low trigger.
<code>L4_IRQ_F_POS_EDGE</code>	Positive edge trigger.
<code>L4_IRQ_F_NEG_EDGE</code>	Negative edge trigger.
<code>L4_IRQ_F_BOTH_EDGE</code>	Both edges trigger.
<code>L4_IRQ_F_MASK</code>	Mask.
<code>L4_IRQ_F_SET_WAKEUP</code>	Wakeup source? Use irq as wakeup source
<code>L4_IRQ_F_CLEAR_WAKEUP</code>	Do not use irq as wakeup source.

Definition at line 70 of file `icu.h`.

### 13.1.10.8.3 Function Documentation

#### 13.1.10.8.3.1 l4\_irq\_bind\_vcpu()

```
l4_msgtag_t l4_irq_bind_vcpu (
    l4_cap_idx_t irq,
    l4_cap_idx_t thread,
    l4_umword_t cfg) [inline]
```

Bind a thread to this Irq for vCPU interrupt forwarding.

If the interrupt is triggered, the kernel will directly inject the interrupt into the guest. This requires that the thread is currently in extended vCPU user mode. Otherwise the interrupt will stay pending and gets injected on the next vCPU user mode transition. Optionally a doorbell Irq can be registered on the thread (see `Thread::register_doorbell_irq()`) that is triggered in this case.

If a guest has acknowledged the interrupt but has not yet issued an EOI (i.e. the interrupt is in "active" state), it is not possible to bind the Irq to a new thread object. Either wait for the guest to issue the EOI or `detach()` from the current thread. In this case the interrupt will stay active in the guest and it is the responsibility of the VMM to handle the eventual EOI of the guest.

## Parameters

<i>irq</i>	The IRQ object that shall be bound.
<i>thread</i>	Thread object this Irq shall be bound to.
<i>cfg</i>	Architecture specific interrupt configuration.

## Returns

Syscall return tag

## Return values

<i>-L4_EPERM</i>	Insufficient permissions; see precondition.
<i>-L4_EBUSY</i>	Cannot bind to new thread because interrupt is active on previous thread and guest has to issue end-of-interrupt first.
<i>-L4_ENOSYS</i>	The kernel does not support direct interrupt forwarding.


## Precondition

The capabilities `irq` and `thread` both must have the permission [L4\\_CAP\\_FPAGE\\_S](#).

Definition at line 300 of file `irq.h`.

References [l4\\_irq\\_bind\\_vcpu\\_u\(\)](#), [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:



### 13.1.10.8.3.2 l4\_irq\_bind\_vcpu\_u()

```

l4_msgtag_t l4_irq_bind_vcpu_u (
    l4_cap_idx_t irq,
    l4_cap_idx_t thread,
    l4_umword_t cfg,
    l4_utcb_t * utcb) [inline]
  
```

Bind a thread to this Irq for vCPU interrupt forwarding.

**Parameters**

<i>irq</i>	The IRQ object that shall be bound. If the interrupt is triggered, the kernel will directly inject the interrupt into the guest. This requires that the thread is currently in extended vCPU user mode. Otherwise the interrupt will stay pending and gets injected on the next vCPU user mode transition. Optionally a doorbell Irq can be registered on the thread (see <code>Thread::register_doorbell_irq()</code> ) that is triggered in this case.
------------	--

If a guest has acknowledged the interrupt but has not yet issued an EOI (i.e. the interrupt is in "active" state), it is not possible to bind the Irq to a new thread object. Either wait for the guest to issue the EOI or `detach()` from the current thread. In this case the interrupt will stay active in the guest and it is the responsibility of the VMM to handle the eventual EOI of the guest.

**Parameters**

<i>thread</i>	Thread object this Irq shall be bound to.
<i>cfg</i>	Architecture specific interrupt configuration.
<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. See <a href="#">l4_utcb</a> .

**Returns**

Syscall return tag

**Return values**

<code>-L4_EPERM</code>	Insufficient permissions; see precondition.
<code>-L4_EBUSY</code>	Cannot bind to the new thread because interrupt is active on previous thread and guest has to issue end-of-interrupt first.
<code>-L4_ENOSYS</code>	The kernel does not support direct interrupt forwarding.

**Precondition**


The invoked Irq capability and the capability `thread` both must have the permission [L4\\_CAP\\_FPAGE\\_S](#).

Definition at line [250](#) of file [irq.h](#).


References [L4\\_CAP\\_FPAGE\\_RWS](#), [l4\\_ipc\\_call\(\)](#), [L4\\_IPC\\_NEVER](#), [l4\\_map\\_obj\\_control\(\)](#), [l4\\_msgtag\(\)](#), [L4\\_NOTHROW](#), [l4\\_obj\\_fpage\(\)](#), [L4\\_PROTO\\_IRQ\\_SENDER](#), [l4\\_msg\\_regs\\_t::mr](#), and [l4\\_fpage\\_t::raw](#).

Referenced by [L4::Irq::bind\\_vcpu\(\)](#), and [l4\\_irq\\_bind\\_vcpu\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 13.1.10.8.3.3 l4\_irq\_detach()

```
l4_msgtag_t l4_irq_detach (
    l4_cap_idx_t irq) [inline]
```

Detach from an interrupt source.

#### Parameters

<i>irq</i>	The IRQ object that shall be detached.
------------	--

#### Returns

Syscall return tag

#### Return values

---



---

0	Successfully detached, there was no interrupt pending.
1	Successfully detached, there was an interrupt pending.
2	Successfully detached, an active vIRQ was abandoned.
-L4_EPERM	Insufficient permissions; see precondition.

#### Precondition

The capability `irq` must have the permission `L4_CAP_FPAGE_S`.


#### Examples

[examples/sys/isr/main.c](#).

Definition at line 294 of file `irq.h`.

References [l4\\_irq\\_detach\\_u\(\)](#), [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:



#### 13.1.10.8.3.4 l4\_irq\_detach\_u()

```

l4_msgtag_t l4_irq_detach_u (
    l4_cap_idx_t irq,
    l4_utcb_t * utcb) [inline]
  
```

Detach from this interrupt.

#### Parameters

<i>irq</i>	The IRQ object that shall be detached.
<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. See <a href="#">l4_utcb</a> .

**Returns**

Syscall return tag

**Return values**

0	Successfully detached, there was no interrupt pending.
1	Successfully detached, there was an interrupt pending.
2	Successfully detached, an active vIRQ was abandoned.
-L4_EPERM	Insufficient permissions; see precondition.

**Precondition**


The invoked Irq capability must have the permission [L4\\_CAP\\_FPAGE\\_S](#).

Definition at line 242 of file [irq.h](#).


References [l4\\_ipc\\_call\(\)](#), [L4\\_IPC\\_NEVER](#), [l4\\_msgtag\(\)](#), [L4\\_NOTHROW](#), and [L4\\_PROTO\\_IRQ\\_SENDER](#).

Referenced by [L4::Irq::detach\(\)](#), and [l4\\_irq\\_detach\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:





### 13.1.10.8.3.5 l4\_irq\_receive()

```
l4_msgtag_t l4_irq_receive (
    l4_cap_idx_t irq,
    l4_timeout_t to) [inline]
```

Unmask and wait for specified IRQ.

#### Parameters

<i>irq</i>	The IRQ object that shall be unmasked.
<i>to</i>	Timeout.

#### Returns


Syscall return tag

Definition at line 313 of file [irq.h](#).


References [l4\\_irq\\_receive\\_u\(\)](#), [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Referenced by [L4Re::Util::Event\\_buffer\\_consumer\\_t< Default\\_event\\_payload >::process\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 13.1.10.8.3.6 l4\_irq\_receive\_u()

```
l4_msgtag_t l4_irq_receive_u (
    l4_cap_idx_t irq,
    l4_timeout_t timeout,
    l4_utcb_t * utcb) [inline]
```

Unmask and wait for this IRQ.

#### Parameters

<i>irq</i>	The IRQ object that shall be unmasked.
<i>timeout</i>	Timeout.
<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. See <a href="#">l4_utcb</a> .

#### Returns

Syscall return tag

#### Note


If this is the function normally used for your IRQs consider using [L4::Semaphore](#) instead of [L4::Irq](#).

Definition at line 270 of file [irq.h](#).


References [l4\\_ipc\\_call\(\)](#), [l4\\_msgtag\(\)](#), [L4\\_NOTHROW](#), and [L4\\_PROTO\\_IRQ](#).

Referenced by [l4\\_irq\\_receive\(\)](#), and [L4::Irq::receive\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



## 13.1.10.8.3.7 l4\_irq\_trigger()

```
l4_msgtag_t l4_irq_trigger (
    l4_cap_idx_t irq) [inline]
```

Trigger an IRQ.

## Parameters

<i>irq</i>	The IRQ object that shall be triggered.
------------	---

## Returns

Syscall return tag.

Note that this function is a send only operation, i.e. there is no return value except for a failed send operation. Especially [l4\\_error\(\)](#) will return an error value from the message tag which still contains the IRQ protocol used for the send operation.


Use [l4\\_ipc\\_error\(\)](#) to check for (send) errors.

Definition at line 307 of file [irq.h](#).

References [l4\\_irq\\_trigger\\_u\(\)](#), [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Referenced by [l4\\_semaphore\\_up\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 13.1.10.8.3.8 l4\_irq\_trigger\_u()

```
l4_msgtag_t l4_irq_trigger_u (
    l4_cap_idx_t irq,
    l4_utcb_t * utcb) [inline]
```

Trigger the object.

#### Parameters

<i>irq</i>	The IRQ object that shall be triggered.
<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. See <a href="#">l4_utcb</a> .

#### Returns


Syscall return tag for a send-only operation, this means there is no return value except [L4\\_MSGTAG\\_ERROR](#) indicating success or failure of the send operation. Use [l4\\_ipc\\_error\(\)](#) to check for errors and **do not** use [l4\\_error\(\)](#).

Definition at line 263 of file [irq.h](#).


References [L4\\_IPC\\_BOTH\\_TIMEOUT\\_0](#), [l4\\_ipc\\_send\(\)](#), [l4\\_msgtag\(\)](#), [L4\\_NOTHROW](#), and [L4\\_PROTO\\_IRQ](#).

Referenced by [l4\\_irq\\_trigger\(\)](#), and [L4::Triggerable::trigger\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



#### 13.1.10.8.3.9 l4\_irq\_unmask()

```
l4_msgtag_t l4_irq_unmask (
    l4_cap_idx_t irq) [inline]
```

Unmask IRQ.

##### Parameters

<i>irq</i>	The IRQ object that shall be unmasked.
------------	--

##### Returns

Syscall return tag


##### Note

[l4\\_irq\\_wait\(\)](#) and [l4\\_irq\\_receive\(\)](#) are doing the unmask themselves.

Definition at line 326 of file [irq.h](#).

References [l4\\_irq\\_unmask\\_u\(\)](#), [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:



#### 13.1.10.8.3.10 l4\_irq\_unmask\_u()

```
l4_msgtag_t l4_irq_unmask_u (
    l4_cap_idx_t irq,
    l4_utcb_t * utcb) [inline]
```

Unmask this IRQ.

##### Parameters

<i>irq</i>	The IRQ object that shall be unmasked.
<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. See <a href="#">l4_utcb</a> .

**Returns**

Syscall return tag for a send-only operation, this means there is no return value except [L4\\_MSGTAG\\_ERROR](#) indicating success or failure of the send operation. Use [l4\\_ipc\\_error\(\)](#) to check for errors and **do not** use [l4\\_error\(\)](#).


`l4q::wait()` and `l4q::receive()` operations already include an `unmask()`, do not use an extra `unmask()` in these cases.

Definition at line 286 of file [irq.h](#).

References [L4\\_IPC\\_NEVER](#), [l4\\_ipc\\_send\(\)](#), [l4\\_msgtag\(\)](#), [L4\\_NOTHROW](#), and [L4\\_PROTO\\_IRQ](#).

Referenced by [l4\\_irq\\_unmask\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:

**13.1.10.8.3.11 l4\_irq\_wait()**

```

l4_msgtag_t l4_irq_wait (
    l4_cap_idx_t irq,
    l4_umword_t * label,
    l4_timeout_t to) [inline]
  
```

Unmask IRQ and wait for any message.

**Parameters**

<i>irq</i>	The IRQ object that shall be unmasked.
<i>label</i>	Receive label.
<i>to</i>	Timeout.

#### Returns

Syscall return tag


#### Examples

[examples/sys/isr/main.c](#).

Definition at line 319 of file [irq.h](#).

References [l4\\_irq\\_wait\\_u\(\)](#), [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:



#### 13.1.10.8.3.12 l4\_irq\_wait\_u()

```

l4_msgtag_t l4_irq_wait_u (
    l4_cap_idx_t irq,
    l4_umword_t * label,
    l4_timeout_t timeout,
    l4_utcb_t * utcb) [inline]

```

Unmask IRQ and (open) wait for any message.

#### Parameters

<i>irq</i>	The IRQ object that shall be unmasked.
<i>label</i>	The <i>protected label</i> shall be received here.
<i>timeout</i>	Timeout.
<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. See <a href="#">l4_utcb</a> .

**Returns**


Syscall return tag

Definition at line 277 of file [irq.h](#).


References [l4\\_ipc\\_send\\_and\\_wait\(\)](#), [l4\\_msgtag\(\)](#), [L4\\_NOTHROW](#), and [L4\\_PROTO\\_IRQ](#).

Referenced by [l4\\_irq\\_wait\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 13.1.10.9 Platform Control C API

C interface for controlling platform-wide properties, see [L4::Platform\\_control](#) for the C++ interface.

Collaboration diagram for Platform Control C API:





## Functions

- `l4_msgtag_t l4_platform_ctl_set_task_asid (l4_cap_idx_t pfc, l4_cap_idx_t task, l4_umword_t asid) L4_NOTHROW`  
*Set ASID of task.*
- `l4_msgtag_t l4_platform_ctl_system_suspend (l4_cap_idx_t pfc, l4_umword_t extras) L4_NOTHROW`  
*Enter suspend to RAM.*
- `l4_msgtag_t l4_platform_ctl_system_shutdown (l4_cap_idx_t pfc, l4_umword_t reboot) L4_NOTHROW`  
*Shutdown or reboot the system.*
- `l4_msgtag_t l4_platform_ctl_cpu_allow_shutdown (l4_cap_idx_t pfc, l4_umword_t phys_id, l4_umword_t enable) L4_NOTHROW`  
*Allow a CPU to be shut down.*
- `l4_msgtag_t l4_platform_ctl_cpu_enable (l4_cap_idx_t pfc, l4_umword_t phys_id) L4_NOTHROW`  
*Enable an offline CPU.*
- `l4_msgtag_t l4_platform_ctl_cpu_disable (l4_cap_idx_t pfc, l4_umword_t phys_id) L4_NOTHROW`  
*Disable an online CPU.*

### 13.1.10.9.1 Detailed Description

C interface for controlling platform-wide properties, see [L4::Platform\\_control](#) for the C++ interface.

#### Include File

```
#include <l4/sys/platform_control.h>
```

The API allows a client to suspend, reboot or shutdown the system.

For the C++ interface refer to [L4::Platform\\_control](#)

### 13.1.10.9.2 Function Documentation

#### 13.1.10.9.2.1 l4\_platform\_ctl\_cpu\_allow\_shutdown()

```
l4_msgtag_t l4_platform_ctl_cpu_allow_shutdown (
    l4_cap_idx_t pfc,
    l4_umword_t phys_id,
    l4_umword_t enable) [inline]
```

Allow a CPU to be shut down.

#### Parameters

<i>pfc</i>	Capability selector for the platform-control object.
<i>phys_id</i>	Physical CPU id of CPU (e.g. local APIC id) to enable.
<i>enable</i>	Allow shutdown when 1, disallow when 0.

**Returns**

Syscall return tag

Definition at line 242 of file [platform\\_control.h](#).

References [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:

**13.1.10.9.2.2 l4\_platform\_ctl\_cpu\_disable()**

```

l4_msgtag_t l4_platform_ctl_cpu_disable (
    l4_cap_idx_t pfc,
    l4_umword_t phys_id) [inline]
  
```

Disable an online CPU.

**Parameters**

<i>pfc</i>	Capability to the platform control object.
<i>phys_id</i>	Physical CPU id of CPU (e.g. local APIC id) to disable.

**Returns**

System call message tag

This function is currently only supported on the ARM EXYNOS platform.

Definition at line 281 of file [platform\\_control.h](#).

References [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:



### 13.1.10.9.2.3 l4\_platform\_ctl\_cpu\_enable()

```
l4_msgtag_t l4_platform_ctl_cpu_enable (
    l4_cap_idx_t pfc,
    l4_umword_t phys_id) [inline]
```

Enable an offline CPU.

#### Parameters

<i>pfc</i>	Capability to the platform control object.
<i>phys_id</i>	Physical CPU id of CPU (e.g. local APIC id) to enable.

#### Returns


System call message tag

This function is currently only supported on the ARM EXYNOS platform.

Definition at line 274 of file [platform\\_control.h](#).

References [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:



### 13.1.10.9.2.4 l4\_platform\_ctl\_set\_task\_asid()

```
l4_msgtag_t l4_platform_ctl_set_task_asid (
    l4_cap_idx_t pfc,
    l4_cap_idx_t task,
    l4_umword_t asid) [inline]
```

Set ASID of task.

On Cortex-R52 platforms, it might be necessary to control the VMID of a task or virtual machine explicitly. The IOMPU on such platforms will use it for further access control of device memory accesses. A privileged component can use this call to control the value.

The caller must have write permissions to the destination task.

**Parameters**

<i>pfc</i>	Capability selector for the platform-control object.
<i>task</i>	Capability selector of destination task
<i>asid</i>	New ASID value


**Returns**

Syscall return tag

Definition at line 62 of file [\\_\\_platform\\_control-arm.h](#).

References [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:

**13.1.10.9.2.5 l4\_platform\_ctl\_system\_shutdown()**

```
l4_msgtag_t l4_platform_ctl_system_shutdown (  
    l4_cap_idx_t pfc,  
    l4_umword_t reboot) [inline]
```

Shutdown or reboot the system.

**Parameters**

<i>pfc</i>	Capability selector for the platform-control object.
<i>reboot</i>	Shutdown when 0, or reboot when 1.


**Returns**

Syscall return tag

Definition at line 221 of file [platform\\_control.h](#).

References [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:

**13.1.10.9.2.6 l4\_platform\_ctl\_system\_suspend()**

```
l4_msgtag_t l4_platform_ctl_system_suspend (
    l4_cap_idx_t pfc,
    l4_umword_t extras) [inline]
```

Enter suspend to RAM.

**Precondition**

Must only be invoked on the boot CPU. Furthermore it must be ensured that the invoking thread is not migrated to a different CPU during the suspend.

**Parameters**

<i>pfc</i>	Capability selector for the platform-control object.
<i>extras</i>	Some extra platform-specific information needed to enter suspend to RAM. On x86 platforms and when using the Platform_control object provided by Fiasco, the value defines the sleep state. The sleep states are defined in the ACPI table. Other platforms as well as lo's Platform_control object don't make use of this value at the moment.


**Returns**

Syscall return tag

Definition at line 214 of file [platform\\_control.h](#).

References [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:

**13.1.10.10 Scheduler**

C interface of the Scheduler kernel object, see [L4::Scheduler](#) for the C++ interface.

Collaboration diagram for Scheduler:

**Data Structures**

- struct [l4\\_sched\\_cpu\\_set\\_t](#)  
*CPU sets.*
- struct [l4\\_sched\\_param\\_t](#)  
*Scheduler parameter set.*

**Typedefs**

- typedef struct [l4\\_sched\\_cpu\\_set\\_t](#) **[l4\\_sched\\_cpu\\_set\\_t](#)**  
*CPU sets.*
- typedef struct [l4\\_sched\\_param\\_t](#) **[l4\\_sched\\_param\\_t](#)**  
*Scheduler parameter set.*

## Enumerations

- enum `L4_scheduler_classes` { `L4_SCHEDULER_CLASS_FIXED_PRIO` = 1UL << 1, `L4_SCHEDULER_CLASS_WFQ` = 1UL << 2 }

*Supported scheduler classes.*

- enum `L4_scheduler_ops` { `L4_SCHEDULER_INFO_OP` = 0UL, `L4_SCHEDULER_RUN_THREAD_OP` = 1UL, `L4_SCHEDULER_IDLE_TIME_OP` = 2UL }

*Operations on the Scheduler object.*

## Functions

- `l4_sched_cpu_set_t l4_sched_cpu_set` (`l4_umword_t` offset, unsigned char granularity, `l4_umword_t` map=1) `L4_NOTHROW`
- `l4_msgtag_t l4_scheduler_info` (`l4_cap_idx_t` scheduler, `l4_umword_t` \*cpu\_max, `l4_sched_cpu_set_t` \*cpus) `L4_NOTHROW`)  
*Get scheduler information.*
- `l4_msgtag_t l4_scheduler_info_with_classes` (`l4_cap_idx_t` scheduler, `l4_umword_t` \*cpu\_max, `l4_sched_cpu_set_t` \*cpus, `l4_umword_t` \*sched\_classes) `L4_NOTHROW`)  
*Get scheduler information.*
- `l4_sched_param_t l4_sched_param` (unsigned prio, `l4_umword_t` quantum=0) `L4_NOTHROW`  
*Construct scheduler parameter.*
- `l4_msgtag_t l4_scheduler_run_thread` (`l4_cap_idx_t` scheduler, `l4_cap_idx_t` thread, `l4_sched_param_t` const \*sp) `L4_NOTHROW`)  
*Run a thread on a Scheduler.*
- `l4_msgtag_t l4_scheduler_idle_time` (`l4_cap_idx_t` scheduler, `l4_sched_cpu_set_t` const \*cpus, `l4_kernel_clock_t` \*us) `L4_NOTHROW`)  
*Query the idle time (in  $\mu$ s) of a CPU.*
- int `l4_scheduler_is_online` (`l4_cap_idx_t` scheduler, `l4_umword_t` cpu) `L4_NOTHROW`  
*Query if a CPU is online.*

### 13.1.10.10.1 Detailed Description

C interface of the Scheduler kernel object, see [L4::Scheduler](#) for the C++ interface.

The Scheduler interface allows a client to manage CPU resources. The API provides functions to query scheduler information, check the online state of CPUs, query CPU idle time and to start threads on defined CPU sets.

The scheduler offers a virtual device IRQ which triggers when the number of online cores changes, e.g. due to hotplug events. In contrast to hardware IRQs, this IRQ implements a limited functionality:

- Only IRQ line 0 is supported, no MSI vectors.
- The IRQ is edge-triggered and the IRQ mode cannot be changed.
- As the IRQ is edge-triggered, it does not have to be explicitly unmasked.

It depends on the platform, which hotplug events actually trigger the IRQ. Many platforms only support triggering the IRQ when a CPU core different from the boot CPU goes online.

## Include File

```
#include <l4/sys/scheduler.h>
```

### 13.1.10.10.2 Enumeration Type Documentation

#### 13.1.10.10.2.1 L4\_scheduler\_classes

enum [L4\\_scheduler\\_classes](#)

Supported scheduler classes.

##### Enumerator

L4_SCHEDULER_CLASS_FIXED_PRIO	Fixed-priority scheduler.
L4_SCHEDULER_CLASS_WFQ	Weighted fair queuing scheduler.

Definition at line [46](#) of file [scheduler.h](#).

#### 13.1.10.10.2.2 L4\_scheduler\_ops

enum [L4\\_scheduler\\_ops](#)

Operations on the Scheduler object.

##### Enumerator

L4_SCHEDULER_INFO_OP	Query infos about the scheduler.
L4_SCHEDULER_RUN_THREAD_OP	Run a thread on this scheduler.
L4_SCHEDULER_IDLE_TIME_OP	Query idle time for the scheduler.

Definition at line [269](#) of file [scheduler.h](#).

### 13.1.10.10.3 Function Documentation

#### 13.1.10.10.3.1 l4\_sched\_cpu\_set()

```
l4_sched_cpu_set_t l4_sched_cpu_set (
    l4_umword_t offset,
    unsigned char granularity,
    l4_umword_t map = 1) [inline]
```

##### Parameters

<i>offset</i>	Offset. Must be a multiple of 2 <sup>granularity</sup> .
<i>granularity</i>	Granularity in log2 notation.
<i>map</i>	Bitmap of CPUs, defaults to 1 in C++.



**Returns**

CPU set.

**Examples**

[examples/sys/migrate/thread\\_migrate.cc](#).

Definition at line 279 of file [scheduler.h](#).

References [l4\\_sched\\_cpu\\_set\\_t::gran\\_offset](#), [L4\\_NOTHROW](#), and [l4\\_sched\\_cpu\\_set\\_t::map](#).

Referenced by [l4\\_sched\\_param\(\)](#).

Here is the caller graph for this function:

**13.1.10.10.3.2 l4\_sched\_param()**

```

l4_sched_param_t l4_sched_param (
    unsigned prio,
    l4_umword_t quantum = 0) [inline]
  
```

Construct scheduler parameter.

**Parameters**

<i>prio</i>	Thread priority (1-255).
<i>quantum</i>	Timeslice in micro seconds.

The [l4\\_sched\\_param\\_t::affinity](#) of the returned value contains all CPUs.

**Examples**

[examples/sys/aliens/main.c](#), [examples/sys/migrate/thread\\_migrate.cc](#), [examples/sys/singlestep/main.c](#), [examples/sys/start-with-exc/main.c](#), and [examples/sys/utcb-ipc/main.c](#).

Definition at line 289 of file [scheduler.h](#).

References [l4\\_sched\\_param\\_t::affinity](#), [L4\\_NOTHROW](#), [l4\\_sched\\_cpu\\_set\(\)](#), [l4\\_sched\\_param\\_t::prio](#), and [l4\\_sched\\_param\\_t::quantum](#).

Here is the call graph for this function:



### 13.1.10.10.3.3 l4\_scheduler\_idle\_time()

```

l4_msgtag_t l4_scheduler_idle_time (
    l4_cap_idx_t scheduler,
    l4_sched_cpu_set_t const * cpus,
    l4_kernel_clock_t * us) [inline]
  
```

Query the idle time (in  $\mu$ s) of a CPU.

#### Parameters

	<i>scheduler</i>	Scheduler object.
	<i>cpus</i>	Set of CPUs to query. Only the idle time of the first selected CPU in <code>cpus.map</code> is queried.
out	<i>us</i>	Idle time of queried CPU in $\mu$ s.

#### Return values

0	Success.
-L4_EINVAL	Invalid CPU requested in cpu set.

This function retrieves the idle time in  $\mu$ s of the first selected CPU in `cpus.map`. The idle time is the accumulated time a CPU has spent in the idle thread since its last reset. To calculate a load estimate `l` one has to retrieve the idle time at the beginning (`i1`) and the end (`i2`) of a known time interval `t`. The load is then calculated as  $l = 1 - (i2 - i1)/t$ .

The idle time is only defined for online CPUs. Reading the idle time from offline CPUs is undefined and may result in either getting -L4\_EINVAL or calculating an estimated (incorrect) load of 1.


#### Note

The idle time statistics of remote CPUs is updated on context switch events only, hence may not be up-to-date when requested cross-CPU. To get up-to-date idle time you should use a thread running on the same CPU of which the idle time is requested.

Definition at line 403 of file [scheduler.h](#).

References [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:



#### 13.1.10.10.3.4 l4\_scheduler\_info()

```

l4_msgtag_t l4_scheduler_info (
    l4_cap_idx_t scheduler,
    l4_umword_t * cpu_max,
    l4_sched_cpu_set_t * cpus) [inline]
  
```

Get scheduler information.

##### Parameters

	<i>scheduler</i>	Scheduler object.
out	<i>cpu_max</i>	Maximum number of CPUs ever available. Optional, can be NULL.
in, out	<i>cpus</i>	<i>cpus.offset</i> is first CPU of interest. <i>cpus.granularity</i> (see <a href="#">l4_sched_cpu_set_t</a> ). <i>cpus.map</i> Bitmap of online CPUs. Must not be NULL.


##### Return values

0	Success.
-L4_ERANGE	The given CPU offset is larger than the maximum number of CPUs.

Definition at line 381 of file [scheduler.h](#).

References [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:



### 13.1.10.10.3.5 l4\_scheduler\_info\_with\_classes()

```
l4_msgtag_t l4_scheduler_info_with_classes (
    l4_cap_idx_t scheduler,
    l4_umword_t * cpu_max,
    l4_sched_cpu_set_t * cpus,
    l4_umword_t * sched_classes) [inline]
```

Get scheduler information.

#### Parameters

	<i>scheduler</i>	Scheduler object.
out	<i>cpu_max</i>	Maximum number of CPUs ever available. Optional, can be NULL.
in, out	<i>cpus</i>	<i>cpus.offset</i> is first CPU of interest. <i>cpus.granularity</i> (see <a href="#">l4_sched_cpu_set_t</a> ). <i>cpus.map</i> Bitmap of online CPUs. Must not be NULL.
out	<i>sched_classes</i>	A bitmap of available scheduling classes (see <a href="#">L4_scheduler_classes</a> ). Optional, can be NULL.

#### Return values


0	Success.
-L4_ERANGE	The given CPU offset is larger than the maximum number of CPUs.

This function delivers the same information as [l4\\_scheduler\\_info](#) plus the available scheduler classes (see [L4\\_scheduler\\_classes](#)).

Definition at line 388 of file [scheduler.h](#).

References [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:



### 13.1.10.10.3.6 l4\_scheduler\_is\_online()

```
int l4_scheduler_is_online (
    l4_cap_idx_t scheduler,
    l4_umword_t cpu) [inline]
```

Query if a CPU is online.

#### Parameters

<i>scheduler</i>	Scheduler object.
<i>cpu</i>	CPU number whose online status should be queried.


#### Return values

<i>true</i>	The CPU is online.
<i>false</i>	The CPU is offline

Definition at line 410 of file [scheduler.h](#).

References [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:



#### 13.1.10.10.3.7 l4\_scheduler\_run\_thread()

```

l4_msgtag_t l4_scheduler_run_thread (
    l4_cap_idx_t scheduler,
    l4_cap_idx_t thread,
    l4_sched_param_t const * sp) [inline]
  
```

Run a thread on a Scheduler.

#### Parameters

<i>scheduler</i>	Scheduler object.
<i>thread</i>	Capability of the thread to run.
<i>sp</i>	Scheduling parameters.

#### Return values

<i>0</i>	Success.
<i>-L4_EINVAL</i>	Invalid size of the scheduling parameter.

This function launches a thread on a CPU determined by the scheduling parameter `sp.affinity`. A thread can be intentionally stopped by migrating it on an offline or an invalid CPU. The thread is only guaranteed to run if the CPU it is migrated to is currently online.

**Note**

If the target CPU is currently not online, there is no guarantee that the thread will ever run, even if the CPU comes online later on.

A scheduler may impose a policy with regard to selecting CPUs. However the scheduler is required to ensure the following two properties:

- Two threads with disjoint CPU sets must be scheduled to different CPUs.
- Two threads with identical CPU sets selecting only a single CPU must be scheduled to the same CPU.

**Examples**

[examples/sys/aliens/main.c](#), [examples/sys/singlestep/main.c](#), [examples/sys/start-with-exc/main.c](#), and [examples/sys/utcb-ipc/main.c](#).

Definition at line 396 of file [scheduler.h](#).

References [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:

**13.1.10.11 Kernel-provided semaphore**

C semaphore interface, see [L4::Semaphore](#) for the C++ interface.

Collaboration diagram for Kernel-provided semaphore:

**Functions**

- [l4\\_msgtag\\_t l4\\_semaphore\\_up \(l4\\_cap\\_idx\\_t sem\) L4\\_NOTHROW](#)  
*Semaphore up operation (wrapper for trigger()).*
- [l4\\_msgtag\\_t l4\\_semaphore\\_down \(l4\\_cap\\_idx\\_t sem, l4\\_timeout\\_t timeout\) L4\\_NOTHROW](#)  
*Semaphore down operation.*

### 13.1.10.11.1 Detailed Description

C semaphore interface, see [L4::Semaphore](#) for the C++ interface.

#### Include File

```
#include <l4/sys/semaphore.h>
```

### 13.1.10.11.2 Function Documentation

#### 13.1.10.11.2.1 l4\_semaphore\_down()

```
l4_msgtag_t l4_semaphore_down (
    l4_cap_idx_t sem,
    l4_timeout_t timeout) [inline]
```

Semaphore down operation.

#### Parameters

<i>sem</i>	Semaphore object.
<i>timeout</i>	Timeout for blocking the semaphore down operation. Note: The receive timeout of this timeout-pair is significant for blocking, the send part is usually non-blocking.

#### Returns

Syscall return tag. Use [l4\\_error\(\)](#) to check for errors.

#### Return values

<code>-L4_EPERM</code>	Insufficient permissions; see precondition.
------------------------	---

#### Precondition


The capability `sem` must have the permission [L4\\_CAP\\_FPAGE\\_S](#).

This method decrements the semaphore counter by one, or blocks if the counter is already zero, until either a timeout or cancel condition hits or the counter is increased by an `up()` operation.

Definition at line 100 of file [semaphore.h](#).

References [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:



### 13.1.10.11.2.2 l4\_semaphore\_up()

```
l4_msgtag_t l4_semaphore_up (
    l4_cap_idx_t sem) [inline]
```

Semaphore up operation (wrapper for trigger()).

#### Parameters

<i>sem</i>	Semaphore object.
------------	-------------------

#### Returns


Send-only IPC message return tag. Use [l4\\_ipc\\_error\(\)](#) to check for errors, do **not** use [l4\\_error\(\)](#).

Increases the semaphore counter by one if it is smaller than an unspecified limit. The unspecified limit is guaranteed to be at least  $2^{31}-1$ .

Definition at line 45 of file [semaphore.h](#).

References [l4\\_irq\\_trigger\(\)](#), and [L4\\_NOTHROW](#).

Here is the call graph for this function:



### 13.1.10.12 Task

C interface of the Task kernel object, see [L4::Task](#) for the C++ interface.

Collaboration diagram for Task:



#### Enumerations

- enum [l4\\_unmap\\_flags\\_t](#) { [L4\\_FP\\_ALL\\_SPACES](#) , [L4\\_FP\\_DELETE\\_OBJ](#) , [L4\\_FP\\_OTHER\\_SPACES](#) }  
*Flags for the unmap operation.*



## Functions

- [l4\\_msgtag\\_t l4\\_task\\_vgicc\\_map](#) ([l4\\_cap\\_idx\\_t](#) task, [l4\\_fpage\\_t](#) vgicc\_fpage) [L4\\_NOTHROW](#)  
*Map the GIC virtual CPU interface page to the task in case Fiasco detected a GIC version 2.*
- [l4\\_msgtag\\_t l4\\_task\\_map](#) ([l4\\_cap\\_idx\\_t](#) dst\_task, [l4\\_cap\\_idx\\_t](#) src\_task, [l4\\_fpage\\_t](#) snd\_fpage, [l4\\_umword\\_t](#) snd\_base) [L4\\_NOTHROW](#)  
*Map resources available in the source task to a destination task.*
- [l4\\_msgtag\\_t l4\\_task\\_unmap](#) ([l4\\_cap\\_idx\\_t](#) task, [l4\\_fpage\\_t](#) fpage, [l4\\_umword\\_t](#) map\_mask) [L4\\_NOTHROW](#)  
*Revoke rights from the task.*
- [l4\\_msgtag\\_t l4\\_task\\_unmap\\_batch](#) ([l4\\_cap\\_idx\\_t](#) task, [l4\\_fpage\\_t](#) const \*fpages, unsigned num\_fpages, [l4\\_umword\\_t](#) map\_mask) [L4\\_NOTHROW](#)  
*Revoke rights from a task.*
- [l4\\_msgtag\\_t l4\\_task\\_delete\\_obj](#) ([l4\\_cap\\_idx\\_t](#) task, [l4\\_cap\\_idx\\_t](#) obj) [L4\\_NOTHROW](#)  
*Release capability and delete object.*
- [l4\\_msgtag\\_t l4\\_task\\_release\\_cap](#) ([l4\\_cap\\_idx\\_t](#) task, [l4\\_cap\\_idx\\_t](#) cap) [L4\\_NOTHROW](#)  
*Release object capability.*
- [l4\\_msgtag\\_t l4\\_task\\_cap\\_valid](#) ([l4\\_cap\\_idx\\_t](#) task, [l4\\_cap\\_idx\\_t](#) cap) [L4\\_NOTHROW](#)  
*Check whether a capability is present (refers to an object).*
- [l4\\_msgtag\\_t l4\\_task\\_cap\\_equal](#) ([l4\\_cap\\_idx\\_t](#) task, [l4\\_cap\\_idx\\_t](#) cap\_a, [l4\\_cap\\_idx\\_t](#) cap\_b) [L4\\_NOTHROW](#)  
*Test whether two capabilities point to the same object with the same permissions (only considering selected permissions).*
- [l4\\_msgtag\\_t l4\\_task\\_add\\_ku\\_mem](#) ([l4\\_cap\\_idx\\_t](#) task, [l4\\_fpage\\_t](#) \*ku\_mem) [L4\\_NOTHROW](#)  
*Add kernel-user memory.*

### 13.1.10.12.1 Detailed Description

C interface of the Task kernel object, see [L4::Task](#) for the C++ interface.

A task represents a combination of the address spaces provided by the [L4Re](#) micro kernel. A task consists of at least a memory address space and an object address space. On IA32 there is also an IO-port address space.

Task objects are created using the [Factory](#) interface.

#### Include File

```
#include <l4/sys/task.h>
```

### 13.1.10.12.2 Enumeration Type Documentation

#### 13.1.10.12.2.1 l4\_unmap\_flags\_t

```
enum l4_unmap_flags_t
```

Flags for the unmap operation.

See also

[L4::Task::unmap\(\)](#) and [l4\\_task\\_unmap\(\)](#)

## Enumerator

L4_FP_ALL_SPACES	<p>Flag to tell the unmap operation to revoke permissions from all child mappings including the mapping in the invoked task.</p> <p><b>Note</b></p> <p>Object capabilities are not hierarchical – they have no children. The result of the map operation on an object capability is a copy of that capability in the object space of the destination task. An unmap operation on object capabilities is a no-op if this flag is not specified.</p> <p><b>See also</b></p> <p><a href="#">L4::Task::unmap()</a> <a href="#">l4_task_unmap()</a></p>
L4_FP_DELETE_OBJ	<p>Flag that indicates that an unmap operation on object capabilities shall try to delete the corresponding objects immediately. This flag implies the <a href="#">L4_FP_ALL_SPACES</a> flag. The concept of deletion is only applicable to kernel objects. Therefore, for memory and I/O port capabilities, this flag has the same effect as <a href="#">L4_FP_ALL_SPACES</a> alone.</p> <p><b>See also</b></p> <p><a href="#">L4::Task::unmap()</a> <a href="#">l4_task_unmap()</a></p> <p><b>Note</b></p> <p>Specifying <a href="#">L4_FP_DELETE_OBJ</a> ^ <a href="#">L4_FP_ALL_SPACES</a> is treated as <a href="#">L4_FP_OTHER_SPACES</a>.</p>
L4_FP_OTHER_SPACES	<p>Counterpart to <a href="#">L4_FP_ALL_SPACES</a>; revoke permissions from child mappings only.</p> <p><b>See also</b></p> <p><a href="#">L4::Task::unmap()</a> <a href="#">l4_task_unmap()</a></p>

Definition at line 167 of file [consts.h](#).

## 13.1.10.12.3 Function Documentation

### 13.1.10.12.3.1 l4\_task\_add\_ku\_mem()

```
l4_msgtag_t l4_task_add_ku_mem (
    l4_cap_idx_t task,
    l4_fpage_t * ku_mem) [inline]
```

Add kernel-user memory.

**Parameters**

	<i>task</i>	Capability selector of the task to add the memory to.
<i>in, out</i>	<i>ku_mem</i>	Flexpage describing the virtual area the memory goes to. On systems without MMU, the flexpage is adjusted to reflect the actually allocated physical address.

**Returns**

Syscall return tag

Kernel-user memory (*ku\_mem*) is memory that is shared between the kernel and user-space. It is needed for the UTCB area of threads (see [l4\\_thread\\_control\\_bind\(\)](#)) and for (extended) vCPU state. Note that existing kernel-user memory cannot be unmapped or mapped somewhere else.

**Note**


The amount of kernel-user memory that can be allocated at once is limited by the used kernel implementation. The minimum allocatable amount is one page ([L4\\_PAGE\\_SIZE](#)). A portable implementation should not depend on allocations greater than 16KiB to succeed.

This function is only guaranteed to work on [L4::Task](#) objects. It might or might not work on [L4::Vm](#) objects or on [L4Re::Dma\\_space](#) objects but there is no practical use for adding kernel-user memory to [L4::Vm](#) objects or to [L4Re::Dma\\_space](#) objects.

Definition at line 497 of file [task.h](#).

References [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:

**13.1.10.12.3.2 l4\_task\_cap\_equal()**

```

l4_msgtag_t l4_task_cap_equal (
    l4_cap_idx_t task,
    l4_cap_idx_t cap_a,
    l4_cap_idx_t cap_b) [inline]
  
```

Test whether two capabilities point to the same object with the same permissions (only considering selected permissions).

**Parameters**

<i>task</i>	Capability selector for the destination task to do the lookup in.
<i>cap↔ _a</i>	Capability selector for the first capability to compare.
<i>cap↔ _b</i>	Capability selector for the second capability to compare.

**Return values**

<i>l4_msgtag_t::label()</i> = 1	The compared capabilities point to the same object with same considered permission.
<i>l4_msgtag_t::label()</i> = 0	The compared capabilities do <b>not</b> point to the same object or differ in the considered permission.


- For [L4::lpc\\_gate](#) objects, only the permissions [L4\\_CAP\\_FPAGE\\_W](#), [L4\\_CAP\\_FPAGE\\_S](#), and [L4\\_FPAGE\\_C\\_OBJ\\_RIGHT1](#) are considered for the comparison. Differences in other permissions are ignored.
- For other objects, only the permissions [L4\\_CAP\\_FPAGE\\_W](#) and [L4\\_CAP\\_FPAGE\\_S](#) are considered for the comparison. Differences in other permissions are ignored.

Note that having the [L4\\_CAP\\_FPAGE\\_R](#) permission is implicit in possessing the capability.

Definition at line [490](#) of file [task.h](#).

References [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:

**13.1.10.12.3.3 l4\_task\_cap\_valid()**

```

l4_msgtag_t l4_task_cap_valid (
    l4_cap_idx_t task,
    l4_cap_idx_t cap) [inline]
  
```

Check whether a capability is present (refers to an object).

**Parameters**

<i>task</i>	Task to check the capability in.
-------------	----------------------------------

<i>cap</i>	Valid capability to check for presence.
------------	---

### Return values

<i>l4_msgtag_t::label()</i> > 0	Capability is present (refers to an object).
<i>l4_msgtag_t::label()</i> == 0	No capability present (void object).

A capability is considered present when it refers to an existing kernel object.


### Precondition

*cap* must be a valid capability index (i.e. not L4\_INVALID\_CAP or the like).

Definition at line 484 of file [task.h](#).

References [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:



#### 13.1.10.12.3.4 l4\_task\_delete\_obj()

```

l4_msgtag_t l4_task_delete_obj (
    l4_cap_idx_t task,
    l4_cap_idx_t obj) [inline]
  
```

Release capability and delete object.

### Parameters

<i>task</i>	Capability selector of destination task.
<i>obj</i>	Capability index of the object to delete.

**Returns**

Syscall return tag

If `obj` has the delete permission, initiates the deletion of the object. This implies that all capabilities for that object are gone afterwards. However, kernel-internally, objects are not destroyed until all other kernel objects holding a reference to it drop the reference. Hence, quota used by that object might not be freed immediately.


If `obj` does not have the delete permission, no error will be reported and only the capability `obj` is removed. (Note that, depending on the object's reference counter, this might still imply initiation of deletion.)

This operation is equivalent to `l4_task_unmap()` with `L4_FP_DELETE_OBJ` flag.

Definition at line 463 of file `task.h`.

References `L4_NOTHROW`, and `l4_utcb()`.

Here is the call graph for this function:

**13.1.10.12.3.5 l4\_task\_map()**

```

l4_msgtag_t l4_task_map (
    l4_cap_idx_t dst_task,
    l4_cap_idx_t src_task,
    l4_fpage_t snd_fpage,
    l4_umword_t snd_base) [inline]
  
```

Map resources available in the source task to a destination task.

**Parameters**

<i>dst_task</i>	Capability selector of the destination task.
<i>src_task</i>	Capability selector of the source task.
<i>snd_fpage</i>	Send flexpage that describes an area in the address space or object space of the source task.
<i>snd_base</i>	Send base that describes an offset in the receive window of the destination task. The lower bits contain additional map control flags (see <code>l4_fpage_cacheability_opt_t</code> for memory mappings, <code>Attributes and additional permissions for object send items</code> for object mappings, and <code>L4_MAP_ITEM_GRANT</code> ; also see <code>l4_map_control()</code> and <code>l4_map_obj_control()</code> ).

**Returns**

Syscall return tag. The function [l4\\_error\(\)](#) shall be used to test if the map operation was successful.

**Return values**

<a href="#">L4_EOK</a>	Operation successful (but see notes below).
<a href="#">-L4_EPERM</a>	Insufficient permissions; see precondition.
<a href="#">-L4_EINVAL</a>	Invalid source task capability.
<a href="#">-L4_IPC_SEMAPFAILED</a>	The map operation failed due to limited quota.

**Precondition**

The capability `dst_task` must have the permission [L4\\_CAP\\_FPAGE\\_W](#).

This method allows for asynchronous transfer of capabilities, memory mappings, and IO-port mappings (on IA32) from one task to another. The receive window is the whole address space of `dst_task`. By specifying proper rights in `snd_fpage` and `snd_base`, it is possible to remove rights during transfer.

**Note**

If the send flexpage is of type [L4\\_FPAGE\\_OBJ](#), the [L4\\_CAP\\_FPAGE\\_S](#) right is removed from the transferred capability unless both the source and destination task capabilities possess the [L4\\_CAP\\_FPAGE\\_S](#) right themselves.

Even with [l4\\_error\(\)](#) returning [L4\\_EOK](#) there might be cases where not all pages of the send flexpage were mapped respectively granted to the destination task, for instance, if the corresponding mapping in the destination task does already exist.

For more information on spaces and mappings, see [Spaces and Mappings](#). The flexpage API is described in more detail at [Flexpages](#).

**Note**

For peculiarities when using grant, see [L4\\_MAP\\_ITEM\\_GRANT](#).

Definition at line 433 of file [task.h](#).


References [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Referenced by [L4::Cap\\_base::copy\(\)](#), and [L4::Cap\\_base::move\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 13.1.10.12.3.6 l4\_task\_release\_cap()

```
l4_msgtag_t l4_task_release_cap (
    l4_cap_idx_t task,
    l4_cap_idx_t cap) [inline]
```

Release object capability.

#### Parameters

<i>task</i>	Capability selector of destination task
<i>cap</i>	Capability selector of object to release

#### Returns

Syscall return tag

This operation unmaps the capability from the specified task. This operation is equivalent to unmapping a single object capability by specifying all object rights as unmap mask.


#### Note

If the reference counter of the kernel object referenced by *cap* goes down to zero, deletion of the object is initiated. Objects are not destroyed until all other kernel objects holding a reference to it drop the reference.

Definition at line 478 of file [task.h](#).

References [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:





**13.1.10.12.3.7 l4\_task\_unmap()**

```
l4_msgtag_t l4_task_unmap (
    l4_cap_idx_t task,
    l4_fpage_t fpage,
    l4_umword_t map_mask) [inline]
```

Revoke rights from the task.

**Parameters**

<i>task</i>	Capability selector of destination task
<i>fpage</i>	Flexpage that describes an area in one capability space of the destination task and the rights to revoke.
<i>map_mask</i>	Unmap mask, see <a href="#">l4_unmap_flags_t</a>

**Returns**

Syscall return tag

This method allows to revoke rights from the destination task. The rights to revoke are specified in the flexpage, see [l4\\_fpage\\_rights\(\)](#). For a flexpage describing IO ports or memory, it also revokes rights from all the tasks that got the rights delegated from the destination task (i.e., this operation does a recursive rights revocation). The capability is unmapped if certain rights are specified, see below for details. It is guaranteed that the rights revocation is completed before this function returns.

Note that this function cannot be used to revoke the reference counting permission (see [L4\\_FPAGE\\_C\\_REF\\_CNT](#)) or the IPC-gate server permission (see [L4\\_FPAGE\\_C\\_IPCGATE\\_SVR](#)) from object capabilities.

It depends on the platform and the object type which rights need to be specified in the *rights* field of *fpage* to unmap a capability:

- An object capability is unmapped if and only if the [L4\\_CAP\\_FPAGE\\_R](#) right bit is set.
- An IO port is unmapped if and only if any right bit is set.
- Memory is unmapped if and only if the [L4\\_FPAGE\\_RO](#) right bit is set.

**Note**

Depending on the page-table features supported by the hardware, revocation of certain rights from a memory capability can be a no-op (i.e., the rights are not revoked). Further, revocation of certain rights may grant other rights which were not present before. For instance, on an architecture without support for NX, revoking X does nothing. For another example, revoking only X from an execute-only page grants read permission (because the mapping remains present in the page table).

If the reference counter of a kernel object referenced in *fpage* goes down to zero (as a result of deleting capabilities), the deletion of the object is initiated. Objects are not destroyed until all other kernel objects holding a reference to it drop the reference.

**Examples**

[examples/sys/utcb-ipc/main.c](#).

Definition at line 440 of file [task.h](#).


References [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Referenced by [L4Re::Util::Cap\\_alloc\\_base::free\(\)](#), [L4Re::Util::Counting\\_cap\\_alloc< COUNTERTYPE, Dbg >::free\(\)](#), and [L4Re::Util::Counting\\_cap\\_alloc< COUNTERTYPE, Dbg >::release\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



#### 13.1.10.12.3.8 l4\_task\_unmap\_batch()

```

l4_msgtag_t l4_task_unmap_batch (
    l4_cap_idx_t task,
    l4_fpage_t const * fpages,
    unsigned num_fpages,
    l4_umword_t map_mask) [inline]
  
```

Revoke rights from a task.

#### Parameters

<i>task</i>	Capability selector of destination task
<i>fpages</i>	An array of flexpages. Each item describes an area in one capability space of the destination task.
<i>num_fpages</i>	The size of the fpages array in elements (number of fpages sent).
<i>map_mask</i>	Unmap mask, see <a href="#">l4_unmap_flags_t</a>

**Returns**

Syscall return tag

Revoke rights specified in an array of flexpages, see [l4\\_task\\_unmap](#) for details.

**Precondition**

The caller needs to take care that num\_fpages is not bigger than L4\_UTCB\_GENERIC\_DATA\_SIZE - 2.

Definition at line 447 of file [task.h](#).

References [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:

**13.1.10.12.3.9 l4\_task\_vgicc\_map()**

```

l4_msgtag_t l4_task_vgicc_map (
    l4_cap_idx_t task,
    l4_fpage_t vgicc_fpage) [inline]
  
```

Map the GIC virtual CPU interface page to the task in case Fiasco detected a GIC version 2.

**Parameters**

<i>task</i>	Capability selector of destination task
<i>vgicc_fpage</i>	Flexpage that describes an area in the address space of the destination task to map the vGICC page to

**Returns**

Syscall return tag

Definition at line 46 of file [\\_\\_task-arm.h](#).


References [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:

**13.1.10.13 Thread**

C Thread object interface, see [L4::Thread](#) for the C++ interface.

Collaboration diagram for Thread:

**Topics**

- [Thread control](#) . . . . . 397  
API for Thread Control method.
- [vCPU API](#) . . . . . 403  
vCPU API.

## Enumerations

- enum `L4_thread_control_flags` { `L4_THREAD_CONTROL_SET_PAGER` = 0x0010000 , `L4_THREAD_CONTROL_BIND_TASK` = 0x0200000 , `L4_THREAD_CONTROL_ALIEN` = 0x0400000 , `L4_THREAD_CONTROL_SET_EXC_HANDLER` = 0x1000000 }
- Flags for the thread control operation.*
- enum `L4_thread_control_mr_indices` { `L4_THREAD_CONTROL_MR_IDX_FLAGS` = 0 , `L4_THREAD_CONTROL_MR_IDX_PAGER` = 1 , `L4_THREAD_CONTROL_MR_IDX_EXC_HANDLER` = 2 , `L4_THREAD_CONTROL_MR_IDX_FLAG_VALS` = 4 , `L4_THREAD_CONTROL_MR_IDX_BIND_UTCB` = 5 , `L4_THREAD_CONTROL_MR_IDX_BIND_TASK` = 6 }
- Indices for the values in the message register for thread control.*
- enum `L4_thread_ex_regs_flags` { `L4_THREAD_EX_REGS_CANCEL` = 0x10000UL , `L4_THREAD_EX_REGS_TRIGGER_EXC` = 0x20000UL , `L4_THREAD_EX_REGS_ARCH_MASK` = 0xff000000UL }
- Flags for the thread ex-regs operation.*
- enum `L4_thread_ex_regs_flags_arm` { `L4_THREAD_EX_REGS_ARM_SET_EL_MASK` = 0x3 << 24 , `L4_THREAD_EX_REGS_ARM_SET_EL_KEEP` = 0x0 << 24 , `L4_THREAD_EX_REGS_ARM_SET_EL_EL0` = 0x1 << 24 , `L4_THREAD_EX_REGS_ARM_SET_EL_EL1` = 0x2 << 24 }
- Arm specific `L4::Thread::ex_regs()` flags.*
- enum `L4_thread_ex_regs_flags_arm64` { `L4_THREAD_EX_REGS_ARM64_SET_EL_MASK` = 0x3 << 24 , `L4_THREAD_EX_REGS_ARM64_SET_EL_KEEP` = 0x0 << 24 , `L4_THREAD_EX_REGS_ARM64_SET_EL_EL0` = 0x1 << 24 , `L4_THREAD_EX_REGS_ARM64_SET_EL_EL1` = 0x2 << 24 }
- Arm64 specific `L4::Thread::ex_regs()` flags.*

## Functions

- `l4_msgtag_t l4_thread_ex_regs` (`l4_cap_idx_t` thread, `l4_addr_t` ip, `l4_addr_t` sp, `l4_umword_t` flags) `L4_NOTHROW`
- Exchange basic thread registers.*
- `l4_msgtag_t l4_thread_ex_regs_u` (`l4_cap_idx_t` thread, `l4_addr_t` ip, `l4_addr_t` sp, `l4_umword_t` flags, `l4_utcb_t` \*utcb) `L4_NOTHROW`
- Exchange basic thread registers.*
- `l4_msgtag_t l4_thread_ex_regs_ret` (`l4_cap_idx_t` thread, `l4_addr_t` \*ip, `l4_addr_t` \*sp, `l4_umword_t` \*flags) `L4_NOTHROW`
- Exchange basic thread registers and return previous values.*
- `l4_msgtag_t l4_thread_ex_regs_ret_u` (`l4_cap_idx_t` thread, `l4_addr_t` \*ip, `l4_addr_t` \*sp, `l4_umword_t` \*flags, `l4_utcb_t` \*utcb) `L4_NOTHROW`
- Exchange basic thread registers and return previous values.*
- `l4_msgtag_t l4_thread_yield` (void) `L4_NOTHROW`
- Yield current time slice.*
- `l4_msgtag_t l4_thread_switch` (`l4_cap_idx_t` to\_thread) `L4_NOTHROW`
- Switch to another thread (and donate the remaining time slice).*
- `l4_msgtag_t l4_thread_stats_time` (`l4_cap_idx_t` thread, `l4_kernel_clock_t` \*us) `L4_NOTHROW`
- Get consumed time of thread in  $\mu$ s.*
- `l4_msgtag_t l4_thread_vcpu_resume_start` (void) `L4_NOTHROW`
- vCPU return from event handler.*
- `l4_msgtag_t l4_thread_vcpu_resume_commit` (`l4_cap_idx_t` thread, `l4_msgtag_t` tag) `L4_NOTHROW`
- Commit vCPU resume.*
- `l4_msgtag_t l4_thread_vcpu_control` (`l4_cap_idx_t` thread, `l4_addr_t` vcpu\_state) `L4_NOTHROW`
- Enable the vCPU feature for the thread.*
- `l4_msgtag_t l4_thread_vcpu_control_u` (`l4_cap_idx_t` thread, `l4_addr_t` vcpu\_state, `l4_utcb_t` \*utcb) `L4_NOTHROW`

- Enable the vCPU feature for the thread.*

  - [l4\\_msgtag\\_t l4\\_thread\\_vcpu\\_control\\_ext](#) ([l4\\_cap\\_idx\\_t](#) thread, [l4\\_addr\\_t](#) ext\_vcpu\_state) [L4\\_NOTHROW](#)

*Enable the extended vCPU feature for the thread.*

  - [l4\\_msgtag\\_t l4\\_thread\\_vcpu\\_control\\_ext\\_u](#) ([l4\\_cap\\_idx\\_t](#) thread, [l4\\_addr\\_t](#) ext\_vcpu\_state, [l4\\_utcb\\_t](#) \*utcb) [L4\\_NOTHROW](#)

*Enable the extended vCPU feature for the thread.*

  - [l4\\_msgtag\\_t l4\\_thread\\_register\\_del\\_irq](#) ([l4\\_cap\\_idx\\_t](#) thread, [l4\\_cap\\_idx\\_t](#) irq) [L4\\_NOTHROW](#)

*Register an IRQ that will trigger upon deletion events.*

  - [l4\\_msgtag\\_t l4\\_thread\\_modify\\_sender\\_start](#) (void) [L4\\_NOTHROW](#)

*Start a thread sender modification sequence.*

  - [int l4\\_thread\\_modify\\_sender\\_add](#) ([l4\\_umword\\_t](#) match\_mask, [l4\\_umword\\_t](#) match, [l4\\_umword\\_t](#) del\_bits, [l4\\_umword\\_t](#) add\_bits, [l4\\_msgtag\\_t](#) \*tag) [L4\\_NOTHROW](#)

*Add a modification pattern to a sender modification sequence.*

  - [l4\\_msgtag\\_t l4\\_thread\\_modify\\_sender\\_commit](#) ([l4\\_cap\\_idx\\_t](#) thread, [l4\\_msgtag\\_t](#) tag) [L4\\_NOTHROW](#)

*Apply (commit) a sender modification sequence.*

  - [l4\\_msgtag\\_t l4\\_thread\\_register\\_doorbell\\_irq](#) ([l4\\_cap\\_idx\\_t](#) thread, [l4\\_cap\\_idx\\_t](#) irq) [L4\\_NOTHROW](#)

*Register an IRQ that will trigger when a forwarded virtual interrupt is pending.*

  - [l4\\_msgtag\\_t l4\\_thread\\_arm\\_set\\_tpidruro](#) ([l4\\_cap\\_idx\\_t](#) thread, [l4\\_addr\\_t](#) tpidruro) [L4\\_NOTHROW](#)

*Set the TPIDRURO thread specific register.*

### 13.1.10.13.1 Detailed Description

C Thread object interface, see [L4::Thread](#) for the C++ interface.

An [L4](#) thread is a thread of execution in the [L4](#) context. Usually user-level and kernel threads are mapped 1:1 to each other. Thread kernel objects are created using a factory, see [Factory](#) ([l4\\_factory\\_create\\_thread\(\)](#)).

Amongst other things an [L4](#) thread encapsulates:

- CPU state
  - General-purpose registers
  - Program counter
  - Stack pointer
- FPU state
- Scheduling parameters, see the [Scheduler](#) API
- Execution state
  - Blocked, Runnable, Running

Thread objects provide an API for

- Thread configuration and manipulation
- Thread switching.

The thread control functions are used to control various aspects of a thread. See [l4\\_thread\\_control\\_start\(\)](#) for more information.

On ARM newly created threads run in EL0 by default and the exception level can be changed there with [ex\\_regs\(\)](#).

#### Include File

```
#include <l4/sys/thread.h>
```

For the C++ interface refer to [L4::Thread](#).

### 13.1.10.13.2 Enumeration Type Documentation

#### 13.1.10.13.2.1 L4\_thread\_control\_flags

```
enum L4_thread_control_flags
```

Flags for the thread control operation.

##### Enumerator

L4_THREAD_CONTROL_SET_PAGER	The pager will be given.
L4_THREAD_CONTROL_BIND_TASK	The task to bind the thread to will be given.
L4_THREAD_CONTROL_ALIEN	Alien state of the thread is set.
L4_THREAD_CONTROL_SET_EXC_HANDLER	The exception handler of the thread will be given.

Definition at line 761 of file [thread.h](#).

#### 13.1.10.13.2.2 L4\_thread\_control\_mr\_indices

```
enum L4_thread_control_mr_indices
```

Indices for the values in the message register for thread control.

##### Enumerator

L4_THREAD_CONTROL_MR_IDX_FLAGS	See also <a href="#">L4_thread_control_flags</a> .
L4_THREAD_CONTROL_MR_IDX_PAGER	Index for pager cap.
L4_THREAD_CONTROL_MR_IDX_EXC_HANDLER	Index for exception handler.
L4_THREAD_CONTROL_MR_IDX_FLAG_VALS	Index for feature values.
L4_THREAD_CONTROL_MR_IDX_BIND_UTCB	Index for UTCB address for bind.
L4_THREAD_CONTROL_MR_IDX_BIND_TASK	Index for task flexpage for bind.

Definition at line 782 of file [thread.h](#).

#### 13.1.10.13.2.3 L4\_thread\_ex\_regs\_flags

```
enum L4_thread_ex_regs_flags
```

Flags for the thread ex-regs operation.

**Enumerator**

L4_THREAD_EX_REGS_CANCEL	Cancel ongoing IPC in the thread.
L4_THREAD_EX_REGS_TRIGGER_EXCEPTION	Trigger artificial exception in thread.
L4_THREAD_EX_REGS_ARCH_MASK	Arch specific flags.

Definition at line 797 of file [thread.h](#).

**13.1.10.13.2.4 L4\_thread\_ex\_regs\_flags\_arm**

```
enum L4_thread_ex_regs_flags_arm
```

Arm specific [L4::Thread::ex\\_regs\(\)](#) flags.

Only one option must be used in calls to [L4::Thread::ex\\_regs\(\)](#). Using more than one option results in undefined behaviour.

**Enumerator**

L4_THREAD_EX_REGS_ARM_SET_EL_MASK	Exception level set mask.
L4_THREAD_EX_REGS_ARM_SET_EL_KEEP	Keep current exception level of thread (default).
L4_THREAD_EX_REGS_ARM_SET_EL_EL0	Set exception level of thread to EL0 (usr mode).
L4_THREAD_EX_REGS_ARM_SET_EL_EL1	Set exception level of thread to EL1 (sys mode).

Definition at line 37 of file [thread.h](#).

**13.1.10.13.2.5 L4\_thread\_ex\_regs\_flags\_arm64**

```
enum L4_thread_ex_regs_flags_arm64
```

Arm64 specific [L4::Thread::ex\\_regs\(\)](#) flags.

Only one option must be used in calls to [L4::Thread::ex\\_regs\(\)](#). Using more than one option results in undefined behaviour.

**Enumerator**

L4_THREAD_EX_REGS_ARM64_SET_EL_MASK	Exception level set mask.
L4_THREAD_EX_REGS_ARM64_SET_EL_KEEP	Keep current exception level of thread (default).
L4_THREAD_EX_REGS_ARM64_SET_EL_EL0	Set exception level of thread to EL0.
L4_THREAD_EX_REGS_ARM64_SET_EL_EL1	Set exception level of thread to EL1t.

Definition at line 44 of file [thread.h](#).



### 13.1.10.13.3 Function Documentation

#### 13.1.10.13.3.1 l4\_thread\_arm\_set\_tpidruro()

```
l4_msgtag_t l4_thread_arm_set_tpidruro (
    l4_cap_idx_t thread,
    l4_addr_t tpidruro) [inline]
```

Set the TPIDRURO thread specific register.

##### Parameters

<i>thread</i>	Thread to manipulate
<i>tpidruro</i>	The value to be set

##### Returns

System call return tag


##### Note

When this function is invoked for a thread currently executing on a different core, then the changed register content will not be visible to that thread until a thread switch happens on that core.

Definition at line 70 of file [thread.h](#).

References [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:



#### 13.1.10.13.3.2 l4\_thread\_ex\_regs()

```
l4_msgtag_t l4_thread_ex_regs (
    l4_cap_idx_t thread,
    l4_addr_t ip,
    l4_addr_t sp,
    l4_umword_t flags) [inline]
```

Exchange basic thread registers.

## Parameters

<i>thread</i>	Capability selector of the thread to manipulate.
<i>ip</i>	New instruction pointer, use <code>~0UL</code> to leave the instruction pointer unchanged.
<i>sp</i>	New stack pointer, use <code>~0UL</code> to leave the stack pointer unchanged.
<i>flags</i>	Ex-regs flags, see <a href="#">L4_thread_ex_regs_flags</a> .

## Returns

System call return tag

This method allows to manipulate and start a thread. The basic functionality is to set the instruction pointer and the stack pointer of a thread. Additionally, this method allows also to cancel ongoing IPC operations and to force the thread to raise an artificial exception (see `flags`). If the thread is in an IPC operation or if [L4\\_THREAD\\_EX\\_REGS\\_TRIGGER\\_EXCEPTION](#) forces an IPC then changes in IP and SP take effect directly after returning from this IPC. On ARM this method allows to change the exception level, see [L4\\_thread\\_ex\\_regs\\_flags\\_arm](#) and [L4\\_thread\\_ex\\_regs\\_flags\\_arm64](#).

The thread is started using [l4\\_scheduler\\_run\\_thread\(\)](#). However, if at the time [l4\\_scheduler\\_run\\_thread\(\)](#) is called, the instruction pointer of the thread is invalid, a later call to [l4\\_thread\\_ex\\_regs\(\)](#) with a valid instruction pointer might start the thread.


## Examples

[examples/sys/aliens/main.c](#), [examples/sys/singlestep/main.c](#), [examples/sys/start-with-exc/main.c](#), and [examples/sys/utcb-ipc/main.c](#).

Definition at line 942 of file [thread.h](#).

References [L4\\_NOTHROW](#), [l4\\_thread\\_ex\\_regs\\_u\(\)](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:



### 13.1.10.13.3.3 l4\_thread\_ex\_regs\_ret()

```

l4_msgtag_t l4_thread_ex_regs_ret (
    l4_cap_idx_t thread,
    l4_addr_t * ip,
    l4_addr_t * sp,
    l4_umword_t * flags) [inline]

```

Exchange basic thread registers and return previous values.

### Parameters

	<i>thread</i>	Capability selector of the thread to manipulate.
in, out	<i>ip</i>	New instruction pointer, use ~0UL to leave the instruction pointer unchanged, return previous instruction pointer.
in, out	<i>sp</i>	New stack pointer, use ~0UL to leave the stack pointer unchanged, returns previous stack pointer.
in, out	<i>flags</i>	Ex-regs flags, see <a href="#">L4_thread_ex_regs_flags</a> , return previous CPU flags of the thread.

### Returns

System call return tag

This method allows to manipulate and start a thread. The basic functionality is to set the instruction pointer and the stack pointer of a thread. Additionally, this method allows also to cancel ongoing IPC operations and to force the thread to raise an artificial exception (see `flags`). If the thread is in an IPC operation or if [L4\\_THREAD\\_EX\\_REGS\\_TRIGGER\\_EXCEPTION](#) forces an IPC then changes in IP and SP take effect directly after returning from this IPC. On ARM this method allows to change the exception level, see [L4\\_thread\\_ex\\_regs\\_flags\\_arm](#) and [L4\\_thread\\_ex\\_regs\\_flags\\_arm64](#).


The thread is started using [l4\\_scheduler\\_run\\_thread\(\)](#). However, if at the time [l4\\_scheduler\\_run\\_thread\(\)](#) is called, the instruction pointer of the thread is invalid, a later call to [l4\\_thread\\_ex\\_regs\(\)](#) with a valid instruction pointer might start the thread.

Returned values are valid only if function returns successfully.

Definition at line 949 of file [thread.h](#).

References [L4\\_NOTHROW](#), [l4\\_thread\\_ex\\_regs\\_ret\\_u\(\)](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:



#### 13.1.10.13.3.4 l4\_thread\_ex\_regs\_ret\_u()

```

l4_msgtag_t l4_thread_ex_regs_ret_u (
    l4_cap_idx_t thread,
    l4_addr_t * ip,
    l4_addr_t * sp,
    l4_umword_t * flags,
    l4_utcb_t * utcb) [inline]
  
```

Exchange basic thread registers and return previous values.

## Parameters

	<i>thread</i>	Capability selector of the thread to manipulate.
in, out	<i>ip</i>	New instruction pointer, use <code>~0UL</code> to leave the instruction pointer unchanged, return previous instruction pointer.
in, out	<i>sp</i>	New stack pointer, use <code>~0UL</code> to leave the stack pointer unchanged, returns previous stack pointer.
in, out	<i>flags</i>	Ex-regs flags, see <a href="#">L4_thread_ex_regs_flags</a> , return previous CPU flags of the thread.
	<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. Defaults to <a href="#">l4_utcb</a> .

## Returns

System call return tag. [out] parameters are only valid if the function returns successfully. Use [l4\\_error\(\)](#) to check.

This method allows to manipulate and start a thread. The basic functionality is to set the instruction pointer and the stack pointer of a thread. Additionally, this method allows also to cancel ongoing IPC operations and to force the thread to raise an artificial exception (see `flags`). If the thread is in an IPC operation or if [L4\\_THREAD\\_EX\\_REGS\\_TRIGGER\\_EXCEPTION](#) forces an IPC then changes in IP and SP take effect directly after returning from this IPC. On ARM this method allows to change the exception level, see [L4\\_thread\\_ex\\_regs\\_flags\\_arm](#) and [L4\\_thread\\_ex\\_regs\\_flags\\_arm64](#).


The thread is started using [L4::Scheduler::run\\_thread\(\)](#). However, if at the time [L4::Scheduler::run\\_thread\(\)](#) is called, the instruction pointer of the thread is invalid, a later call to `ex_regs()` with a valid instruction pointer might start the thread.

Definition at line 823 of file [thread.h](#).


References [L4\\_NOTHROW](#), [l4\\_thread\\_ex\\_regs\\_u\(\)](#), and [l4\\_msg\\_regs\\_t::mr](#).

Referenced by [L4::Thread::ex\\_regs\(\)](#), and [l4\\_thread\\_ex\\_regs\\_ret\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



13.1.10.13.3.5 `l4_thread_ex_regs_u()`

```
l4_msgtag_t l4_thread_ex_regs_u (
    l4_cap_idx_t thread,
    l4_addr_t ip,
    l4_addr_t sp,
    l4_umword_t flags,
    l4_utcb_t * utcb) [inline]
```

Exchange basic thread registers.

**Parameters**

<i>thread</i>	Capability selector of the thread to manipulate.
<i>ip</i>	New instruction pointer, use <code>~0UL</code> to leave the instruction pointer unchanged.
<i>sp</i>	New stack pointer, use <code>~0UL</code> to leave the stack pointer unchanged.
<i>flags</i>	Ex-regs flags, see <a href="#">L4_thread_ex_regs_flags</a> .
<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. Defaults to <a href="#">l4_utcb</a> .

**Returns**

System call return tag.

This method allows to manipulate and start a thread. The basic functionality is to set the instruction pointer and the stack pointer of a thread. Additionally, this method allows also to cancel ongoing IPC operations and to force the thread to raise an artificial exception (see `flags`). If the thread is in an IPC operation or if [L4\\_THREAD\\_EX\\_REGS\\_TRIGGER\\_EXCEPTION](#) forces an IPC then changes in IP and SP take effect directly after returning from this IPC. On ARM this method allows to change the exception level, see [L4\\_thread\\_ex\\_regs\\_flags\\_arm](#) and [L4\\_thread\\_ex\\_regs\\_flags\\_arm64](#).


The thread is started using [L4::Scheduler::run\\_thread\(\)](#). However, if at the time [L4::Scheduler::run\\_thread\(\)](#) is called, the instruction pointer of the thread is invalid, a later call to `ex_regs()` with a valid instruction pointer might start the thread.

Definition at line 812 of file [thread.h](#).


References [l4\\_ipc\\_call\(\)](#), [L4\\_IPC\\_NEVER](#), [l4\\_msgtag\(\)](#), [L4\\_NOTHROW](#), [L4\\_PROTO\\_THREAD](#), [L4\\_THREAD\\_EX\\_REGS\\_OP](#), and [l4\\_msg\\_regs\\_t::mr](#).

Referenced by [L4::Thread::ex\\_regs\(\)](#), [l4\\_thread\\_ex\\_regs\(\)](#), and [l4\\_thread\\_ex\\_regs\\_ret\\_u\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 13.1.10.13.3.6 l4\_thread\_modify\_sender\_add()

```

int l4_thread_modify_sender_add (
    l4_umword_t match_mask,
    l4_umword_t match,
    l4_umword_t del_bits,
    l4_umword_t add_bits,
    l4_msgtag_t * tag) [inline]

```

Add a modification pattern to a sender modification sequence.

#### Parameters

<i>tag</i>	Tag received from <a href="#">l4_thread_modify_sender_start()</a> or previous <a href="#">l4_thread_modify_sender_add()</a> calls from the same sequence.
<i>match_mask</i>	Bitmask of bits to match the label.
<i>match</i>	Bitmask that must be equal to the label after applying <i>match_mask</i> .
<i>del_bits</i>	Bits to be deleted from the label.
<i>add_bits</i>	Bits to be added to the label.

#### Returns

0 on success, <0 on error

In pseudo code: if ((sender\_label & match\_mask) == match) { sender\_label = (sender\_label & ~del\_bits) | add\_bits; }

Only the first match is applied.


#### See also

[l4\\_thread\\_modify\\_sender\\_start](#)  
[l4\\_thread\\_modify\\_sender\\_commit](#)

Definition at line 1116 of file [thread.h](#).

References [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:



#### 13.1.10.13.3.7 l4\_thread\_modify\_sender\_commit()

```

l4_msgtag_t l4_thread_modify_sender_commit (
    l4_cap_idx_t thread,
    l4_msgtag_t tag) [inline]
  
```

Apply (commit) a sender modification sequence.

The modification rules are applied to all IPCs to the thread (whether directly or by IPC gate) that are already in flight, that is that the sender is already blocking on.

##### Note

Modifying the senders of a thread running on a different CPU core is not supported.

To ensure that no in-flight senders are missed, either the thread itself must execute `modify_senders`, or the thread executing the `modify_senders` must synchronize with the target thread. This synchronization must ensure the following:

1. Before `modify_senders` is executed the target thread must execute at least shortly (so that pending DRQs are handled).
2. The target thread must pause its IPC dispatch, until `modify_senders` is completed. In other words, the target thread must not be receive ready, because otherwise an IPC message with an unmodified label can be transferred to its UTCB or vCPU state.

##### See also


[l4\\_thread\\_modify\\_sender\\_start](#)

[l4\\_thread\\_modify\\_sender\\_add](#)

Definition at line 1127 of file [thread.h](#).

References [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:



### 13.1.10.13.3.8 l4\_thread\_modify\_sender\_start()

```
l4_msgtag_t l4_thread_modify_sender_start (  
    void )    [inline]
```

Start a thread sender modification sequence.

Add modification rules with [l4\\_thread\\_modify\\_sender\\_add\(\)](#) and commit with [l4\\_thread\\_modify\\_sender\\_commit\(\)](#). Do not touch the UTCB between [l4\\_thread\\_modify\\_sender\\_start\(\)](#) and [l4\\_thread\\_modify\\_sender\\_commit\(\)](#).

This mechanism shall be used to change the source object labels of every pending IPC of an IPC gate or an IRQ if the labels in such pending IPC become invalid for the receiving thread, potentially because:

- an IPC gate / IRQ was unbound from a thread, or
- an IPC gate / IRQ was removed, or
- the label of an IPC gate /IRQ bound to a thread was changed.

It is not required to perform the modify\_sender mechanism after an IPC gate or an IRQ was bound to a thread for the first time.

See also


[l4\\_thread\\_modify\\_sender\\_add](#)

[l4\\_thread\\_modify\\_sender\\_commit](#)

Definition at line 1110 of file [thread.h](#).

References [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:





#### 13.1.10.13.3.9 l4\_thread\_register\_del\_irq()

```
l4_msgtag_t l4_thread_register_del_irq (  
    l4_cap_idx_t thread,  
    l4_cap_idx_t irq) [inline]
```

Register an IRQ that will trigger upon deletion events.

##### Parameters

<i>thread</i>	Thread to register IRQ for.
<i>irq</i>	Capability selector for the IRQ object to be triggered.

##### Returns

System call return tag containing the return code.

##### Return values

<code>-L4_EPERM</code>	Insufficient permissions; see precondition.
------------------------	---

##### Precondition

The capability `irq` must have the permission `L4_CAP_FPAGE_W`.

In case the `irq` is already bound to an interrupt source, it is unbound first. When `irq` is deleted, it will be deregistered first. A registered deletion Irq can only be deregistered by deleting the Irq or the thread.

List of deletion events:


- deletion of one or several IPC gates bound to this thread.

When the deletion event is delivered, there is no indication about which IPC gate was deleted.

Definition at line 1037 of file `thread.h`.

References `L4_NOTHROW`, and `l4_utcb()`.

Here is the call graph for this function:



### 13.1.10.13.3.10 l4\_thread\_register\_doorbell\_irq()

```
l4_msgtag_t l4_thread_register_doorbell_irq (  
    l4_cap_idx_t thread,  
    l4_cap_idx_t irq) [inline]
```

Register an IRQ that will trigger when a forwarded virtual interrupt is pending.

#### Parameters

<i>thread</i>	Thread to register IRQ for.
<i>irq</i>	Capability selector for the IRQ object to be triggered.

#### Returns

System call return tag containing the return code.

#### Return values

<i>-L4_EPERM</i>	Insufficient permissions; see precondition.
------------------	---

#### Precondition

The capability `irq` must have the permission [L4\\_CAP\\_FPAGE\\_W](#).


See [l4\\_irq\\_bind\\_vcpu\(\)](#) for more details about how interrupts can be forwarded directly by the kernel to extended vCPU user mode.

In case the `irq` is already bound to an interrupt source, it is unbound first. When `irq` is deleted, it will be deregistered first. A registered deletion `l4r` can only be deregistered by deleting the `l4r` or the thread.

Definition at line 1146 of file [thread.h](#).

References [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:



#### 13.1.10.13.3.11 l4\_thread\_stats\_time()

```
l4_msgtag_t l4_thread_stats_time (
    l4_cap_idx_t thread,
    l4_kernel_clock_t * us) [inline]
```

Get consumed time of thread in  $\mu$ s.

##### Parameters

	<i>thread</i>	Thread to get the consumed time from.
out	<i>us</i>	Consumed time in $\mu$ s.


##### Returns

system call return tag

Definition at line 1005 of file [thread.h](#).

References [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:



#### 13.1.10.13.3.12 l4\_thread\_switch()

```
l4_msgtag_t l4_thread_switch (
    l4_cap_idx_t to_thread) [inline]
```

Switch to another thread (and donate the remaining time slice).

##### Parameters

<i>to_thread</i>	The thread to switch to.
------------------	--------------------------

**Returns**

system call return tag

Definition at line 996 of file [thread.h](#).

References [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:

**13.1.10.13.3.13 l4\_thread\_vcpu\_control()**

```
l4_msgtag_t l4_thread_vcpu_control (  
    l4_cap_idx_t thread,  
    l4_addr_t vcpu_state) [inline]
```

Enable the vCPU feature for the thread.

**Parameters**

<i>thread</i>	Capability selector of the thread for which the vCPU feature shall be enabled.
<i>vcpu_state</i>	The virtual address where the kernel shall store the vCPU state in case of vCPU exits. The address must be a valid kernel-user-memory address (see <a href="#">l4_task_add_ku_mem()</a> ).

**Returns**

Syscall return tag.

This function enables the vCPU feature of the `thread`.

The kernel-user memory area starting at `vcpu_state` must be at least 128-byte aligned and must cover the size of [l4\\_vcpu\\_state\\_t](#).


**Note**

Disabling of the vCPU feature is optional and currently not supported.

Definition at line 1054 of file [thread.h](#).

References [L4\\_NOTHROW](#), [l4\\_thread\\_vcpu\\_control\\_u\(\)](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:

**13.1.10.13.3.14 l4\_thread\_vcpu\_control\_ext()**

```

l4_msgtag_t l4_thread_vcpu_control_ext (
    l4_cap_idx_t thread,
    l4_addr_t ext_vcpu_state) [inline]
  
```

Enable the extended vCPU feature for the thread.

**Parameters**

<i>thread</i>	Capability selector of the thread for which the extended vCPU feature shall be enabled.
<i>ext_vcpu_state</i>	The virtual address where the kernel shall store the vCPU state in case of vCPU exits. The address must be a valid kernel-user-memory address (see <a href="#">l4_task_add_ku_mem()</a> ).

**Returns**

Syscall return tag.

The extended vCPU feature allows the use of hardware-virtualization features such as Intel's VT or AMD's SVM.

This function enables the extended vCPU feature of the `thread`. Enabling the extended vCPU feature also enables the vCPU feature.

The kernel-user memory area starting at `ext_vcpu_state` must be at least 4 KiB aligned and must cover a size of `L4_PAGESIZE`. It includes the data of [l4\\_vcpu\\_state\\_t](#) at offset 0, the extended vCPU state at offset `L4_VCPU_OFFSET_EXT_STATE`, and, on some platforms, the extended vCPU information at offset `L4_VCPU_OFFSET_EXT_INFOS`.

**Note**

Enabling the extended vCPU feature for a thread running on a different CPU core is currently not supported.


Disabling of the extended vCPU feature is currently not supported.

Upgrading from non-extended vCPU feature to extended vCPU feature is currently not supported.

Definition at line 1069 of file [thread.h](#).

References [L4\\_NOTHROW](#), [l4\\_thread\\_vcpu\\_control\\_ext\\_u\(\)](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:



### 13.1.10.13.3.15 l4\_thread\_vcpu\_control\_ext\_u()

```

l4_msgtag_t l4_thread_vcpu_control_ext_u (
    l4_cap_idx_t thread,
    l4_addr_t ext_vcpu_state,
    l4_utcb_t * utcb) [inline]
  
```

Enable the extended vCPU feature for the thread.

**Parameters**

<i>thread</i>	Capability selector of the thread for which the extended vCPU feature shall be enabled.
<i>ext_vcpu_state</i>	The virtual address where the kernel shall store the vCPU state in case of vCPU exits. The address must be a valid kernel-user-memory address (see <a href="#">L4::Task::add_ku_mem()</a> ).
<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. Defaults to <a href="#">l4_utcb</a> .

**Returns**

Syscall return tag.

The extended vCPU feature allows the use of hardware-virtualization features such as Intel's VT-x (VMX) or AMD's AMD-V (SVM).

This function enables the extended vCPU feature of `this` thread. Enabling the extended vCPU feature also enables the vCPU feature.

The kernel-user memory area starting at `ext_vcpu_state` must be at least 4 KiB aligned and must cover a size of `L4_PAGESIZE`. It includes the data of [l4\\_vcpu\\_state\\_t](#) at offset 0, the extended vCPU state at offset `L4_VCPU↵_OFFSET_EXT_STATE`, and, on some platforms, the extended vCPU information at offset `L4_VCPU_OFFSET_↵EXT_INFOS`.

On Intel's VT-x (VMX), the extended vCPU state is [l4\\_vm\\_vmx\\_vcpu\\_vmcs\\_t](#) and the extended vCPU information is [l4\\_vm\\_vmx\\_vcpu\\_infos\\_t](#). Furthermore, the extended vCPU state needs to be associated with a vCPU context (see [l4\\_vm\\_vmx\\_set\\_hw\\_vmcs\(\)](#)).

On AMD's AMD-V (SVM), the extended vCPU state is [l4\\_vm\\_svm\\_vmcb\\_t](#).

**Note**

Enabling the extended vCPU feature for a thread running on a different CPU core is currently not supported.

Disabling of the extended vCPU feature is currently not supported.


Upgrading from non-extended vCPU feature to extended vCPU feature is currently not supported.

Definition at line 1059 of file [thread.h](#).


References [l4\\_ipc\\_call\(\)](#), [L4\\_IPC\\_NEVER](#), [l4\\_msgtag\(\)](#), [L4\\_NOTHROW](#), [L4\\_PROTO\\_THREAD](#), and [l4\\_msg\\_regs\\_t::mr](#).

Referenced by [l4\\_thread\\_vcpu\\_control\\_ext\(\)](#), and [L4::Thread::vcpu\\_control\\_ext\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 13.1.10.13.3.16 l4\_thread\_vcpu\_control\_u()

```

l4_msgtag_t l4_thread_vcpu_control_u (
    l4_cap_idx_t thread,
    l4_addr_t vcpu_state,
    l4_utcb_t * utcb) [inline]
  
```

Enable the vCPU feature for the thread.

**Parameters**

<i>thread</i>	Capability selector of the thread for which the vCPU feature shall be enabled.
---------------	--

<i>vcpu_state</i>	A virtual address pointing to a <a href="#">l4_vcpu_state_t</a> . It must be a valid kernel-user-memory address (see <a href="#">L4::Task::add_ku_mem()</a> ).
<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. Defaults to <a href="#">l4_utcb</a> .

### Returns

Syscall return tag.

This function enables the vCPU feature of `this` thread

The kernel-user memory starting at `vcpu_state` must be at least 128-byte aligned and must cover the size of [l4\\_vcpu\\_state\\_t](#).

The asynchronous IPC handling is described at [vCPU API](#).

### Note


Disabling of the vCPU feature is optional and currently not supported.

Definition at line [1044](#) of file [thread.h](#).


References [l4\\_ipc\\_call\(\)](#), [L4\\_IPC\\_NEVER](#), [l4\\_msgtag\(\)](#), [L4\\_NOTHROW](#), [L4\\_PROTO\\_THREAD](#), [L4\\_THREAD\\_VCPU\\_CONTROL\\_ON](#) and [l4\\_msg\\_regs\\_t::mr](#).

Referenced by [l4\\_thread\\_vcpu\\_control\(\)](#), and [L4::Thread::vcpu\\_control\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:





### 13.1.10.13.3.17 l4\_thread\_vcpu\_resume\_commit()

```
l4_msgtag_t l4_thread_vcpu_resume_commit (
    l4_cap_idx_t thread,
    l4_msgtag_t tag) [inline]
```

Commit vCPU resume.

#### Parameters

<i>thread</i>	Thread to be resumed, the invalid cap can be used for the current thread.
<i>tag</i>	Tag to use, returned by <a href="#">l4_thread_vcpu_resume_start()</a>

#### Returns

Syscall return tag containing one of the following return codes.

#### Return values

0	Indicates a VM exit, provided that <i>thread</i> is in extended vCPU mode with virtual interrupts cleared.
1	Indicates an incoming IPC message, provided that the <i>thread</i> is in extended vCPU mode with virtual interrupts cleared.
-L4_EPERM	The user task capability set in the vCPU state is missing the <a href="#">L4_CAP_FPAGE_S</a> right. On Intel's VT-x (VMX): The vCPU context capability set in the extended vCPU state is missing the <a href="#">L4_CAP_FPAGE_S</a> right.
-L4_ENOENT	The user task capability set in the vCPU state is invalid.
-L4_EINVAL	<i>thread</i> is not the current running thread, or does not have the vCPU feature enabled. On Intel's VT-x (VMX): No vCPU context associated with the extended vCPU state.
-L4_EBUSY	On Intel's VT-x (VMX): The vCPU context associated with the extended vCPU state is already active on a different CPU.
-L4_ENODEV	On Intel's VT-x (VMX): The vCPU context associated with the extended vCPU state cannot be initialized or activated.
<0	A supplied mapping failed.

All flexpages in the UTCB (added with [l4\\_sndfpage\\_add\(\)](#) after [l4\\_thread\\_vcpu\\_resume\\_start\(\)](#)) are unconditionally mapped into the user task configured in the vCPU state.

To resume into another address space, the capability to the target [Task](#) (or [L4::Vm](#)) must be set in [l4\\_vcpu\\_state\\_t::user\\_task](#) together with [L4\\_VCPU\\_F\\_USER\\_MODE](#). The capability selector must have all lower bits clear (see [L4\\_CAP\\_MASK](#)). The kernel adds the [L4\\_SYSF\\_SEND](#) flag there to indicate that the capability has been referenced in the kernel. Consecutive resumes will not reference the task capability again until all lower bits are cleared again. To release a task use a different task capability or use an invalid capability with the [L4\\_SYSF\\_REPLY](#) flag set.


See also

[l4\\_vcpu\\_state\\_t](#)

Definition at line 1017 of file [thread.h](#).

References [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:



#### 13.1.10.13.3.18 l4\_thread\_vcpu\_resume\_start()

```
l4_msgtag_t l4_thread_vcpu_resume_start (
    void ) [inline]
```

vCPU return from event handler.

Returns


Message tag to be used for [l4\\_sndfpage\\_add\(\)](#) and [l4\\_thread\\_vcpu\\_resume\\_commit\(\)](#)

The vCPU resume functionality is split in multiple functions to allow the specification of additional send-flexpages using [l4\\_sndfpage\\_add\(\)](#).

Definition at line 1011 of file [thread.h](#).

References [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:



**13.1.10.13.3.19 l4\_thread\_yield()**

```
l4_msgtag_t l4_thread_yield (
    void ) [inline]
```

Yield current time slice.


**Returns**

system call return tag

Definition at line 891 of file [thread.h](#).

References [L4\\_INVALID\\_CAP](#), [L4\\_IPC\\_BOTH\\_TIMEOUT\\_0](#), [l4\\_ipc\\_receive\(\)](#), [l4\\_msgtag\(\)](#), and [L4\\_NOTHROW](#).

Here is the call graph for this function:

**13.1.10.13.4 Thread control**

API for Thread Control method.

Collaboration diagram for Thread control:

**Functions**

- void [l4\\_thread\\_control\\_start](#) (void) [L4\\_NOTHROW](#)  
*Start a thread control API sequence.*
- void [l4\\_thread\\_control\\_pager](#) ([l4\\_cap\\_idx\\_t](#) pager) [L4\\_NOTHROW](#)  
*Set the pager.*
- void [l4\\_thread\\_control\\_exc\\_handler](#) ([l4\\_cap\\_idx\\_t](#) exc\_handler) [L4\\_NOTHROW](#)  
*Set the exception handler.*
- void [l4\\_thread\\_control\\_bind](#) ([l4\\_utcb\\_t](#) \*thread\_utcb, [l4\\_cap\\_idx\\_t](#) task) [L4\\_NOTHROW](#)  
*Bind the thread to a task.*
- void [l4\\_thread\\_control\\_alien](#) (int on) [L4\\_NOTHROW](#)  
*Enable alien mode.*
- [l4\\_msgtag\\_t](#) [l4\\_thread\\_control\\_commit](#) ([l4\\_cap\\_idx\\_t](#) thread) [L4\\_NOTHROW](#)  
*Commit the thread control parameters.*

#### 13.1.10.13.4.1 Detailed Description

API for Thread Control method.

The thread control API provides access to almost any parameter of a thread object. The API is based on a single invocation of the thread object. However, because of the huge amount of parameters, the API provides a set of functions to set specific parameters of a thread and a commit function to commit the thread control call (see [l4\\_thread\\_control\\_commit\(\)](#)).

A thread control operation must always start with [l4\\_thread\\_control\\_start\(\)](#) and be committed with [l4\\_thread\\_control\\_commit\(\)](#). All other thread control parameter setter functions must be called between these two functions.

An example for a sequence of thread control API calls can be found below.

```
l4\_thread\_control\_start\(\);
l4\_thread\_control\_pager\(pager\_cap\);
l4\_thread\_control\_bind \(thread\_utcb, task\);
l4\_thread\_control\_commit\(thread\_cap\);
```

#### 13.1.10.13.4.2 Function Documentation

##### **[l4\\_thread\\_control\\_alien\(\)](#)**

```
void l4_thread_control_alien (
    int on) [inline]
```

Enable alien mode.

##### **Parameters**

<i>on</i>	Boolean value defining the state of the feature.
-----------	--

For a thread in alien mode the kernel produces just an exception IPC for each IPC and exception caused by the alien thread instead of handling these events regularly. (Page faults of alien threads and interrupts occurring while the alien thread is running are always handled regularly.) While the alien thread is blocking, the exception handler can inspect and modify the state of the alien thread and potentially also the system call arguments. If the exception handler replies with [L4\\_PROTO\\_ALLOW\\_SYSCALL](#) as message tag, the kernel handles the next IPC or exception of the alien thread in a regular way. If the exception handler leaves certain thread state unchanged (in particular the instruction pointer), this will be the IPC or exception that caused the call of the exception handler. For a regularly processed IPC or exception of the alien thread the kernel also performs an exception IPC on kernel exit.

This feature can be used to attach a debugger to a thread and trace all object invocations and their results. It could also be used to handle other systems that use the same syscall instruction as [L4Re](#).


##### **Examples**

[examples/sys/aliens/main.c](#), and [examples/sys/singlestep/main.c](#).

Definition at line 981 of file [thread.h](#).

References [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:



### **`l4_thread_control_bind()`**

```
void l4_thread_control_bind (
    l4_utcb_t * thread_utcb,
    l4_cap_idx_t task) [inline]
```

Bind the thread to a task.

#### **Parameters**

<i>thread_utcb</i>	The thread's UTCB address within the task it shall be bound to. The address must be aligned (architecture dependent; at least word aligned) and it must point to at least <a href="#">L4_UTCB_OFFSET</a> bytes of kernel-user memory.
<i>task</i>	The task the thread shall be bound to.

#### **Precondition**

The thread must not be bound to a task yet.

The capability `task` must have the permission [L4\\_CAP\\_FPAGE\\_S](#), otherwise the later call to [l4\\_thread\\_control\\_commit\(\)](#) will fail with [L4\\_EPERM](#).

A thread may execute code in the context of a task if and only if the thread is bound to the task. To actually start execution, [l4\\_thread\\_ex\\_regs\(\)](#) needs to be used. Execution in the context of the task means that the code has access to all the task's resources (and only those). The executed code itself must be one of those resources. A thread can be bound at most once to a task.

#### **Note**

The UTCBs of different threads in the same task should not overlap in order to prevent data corruption.


#### **Examples**

[examples/sys/aliens/main.c](#), [examples/sys/singlestep/main.c](#), [examples/sys/start-with-exc/main.c](#), and [examples/sys/utcb-ipc/main.c](#).

Definition at line 975 of file [thread.h](#).

References [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:



### **l4\_thread\_control\_commit()**

```
l4_msgtag_t l4_thread_control_commit (
    l4_cap_idx_t thread) [inline]
```

Commit the thread control parameters.

#### **Parameters**

<i>thread</i>	Capability selector of target thread to commit to.
---------------	--

#### **Returns**

Syscall return tag containing one of the following return codes.

#### **Return values**

<i>L4_EOK</i>	Operation successful.
<i>-L4_EPERM</i>	Insufficient permissions; see precondition.
<i>-L4_EINVAL</i>	Malformed thread control parameters.

#### **Precondition**

The capability `thread` must have the permission [L4\\_CAP\\_FPAGE\\_S](#). When using [l4\\_thread\\_control\\_bind\(\)](#), also the respective task capability must have the permission [L4\\_CAP\\_FPAGE\\_S](#).

#### **Examples**

[examples/sys/aliens/main.c](#), [examples/sys/singlestep/main.c](#), [examples/sys/start-with-exc/main.c](#), and [examples/sys/utcb-ipc/main.c](#).

Definition at line 987 of file [thread.h](#).

References [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:



### **`l4_thread_control_exc_handler()`**

```
void l4_thread_control_exc_handler (
    l4_cap_idx_t exc_handler) [inline]
```

Set the exception handler.

#### **Parameters**

<i>exc_handler</i>	Capability selector invoked to send an exception IPC.
--------------------	---

#### **Note**

The exception-handler capability selector is interpreted in the task the thread is bound to (executes in).


#### **Examples**

[examples/sys/aliens/main.c](#), [examples/sys/singlestep/main.c](#), [examples/sys/start-with-exc/main.c](#), and [examples/sys/utcb-ipc/main.c](#).

Definition at line 968 of file [thread.h](#).

References [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:



## **l4\_thread\_control\_pager()**

```
void l4_thread_control_pager (  
    l4_cap_idx_t pager) [inline]
```

Set the pager.

### **Parameters**

<i>pager</i>	Capability selector invoked to send a page-fault IPC.
--------------	---

### **Note**

The pager capability selector is interpreted in the task the thread is bound to (executes in).

### **Examples**

[examples/sys/aliens/main.c](#), [examples/sys/singlestep/main.c](#), [examples/sys/start-with-exc/main.c](#), and [examples/sys/utcb-ipc/main.c](#).

Definition at line 962 of file [thread.h](#).

References [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:



## **l4\_thread\_control\_start()**

```
void l4_thread_control_start (  
    void ) [inline]
```

Start a thread control API sequence.

This function starts a sequence of thread control API functions. After this functions any of following functions may be called in any order.

- [l4\\_thread\\_control\\_pager\(\)](#)
- [l4\\_thread\\_control\\_exc\\_handler\(\)](#)
- [l4\\_thread\\_control\\_bind\(\)](#)
- [l4\\_thread\\_control\\_alien\(\)](#)

To commit the changes to the thread [l4\\_thread\\_control\\_commit\(\)](#) must be called in the end.



**Note**

The thread control API calls store the parameters for the thread in the UTCB of the caller (see [l4\\_utcb\(\)](#)), this means between [l4\\_thread\\_control\\_start\(\)](#) and [l4\\_thread\\_control\\_commit\(\)](#) no functions that modify the UTCB contents must be called.

**Examples**

[examples/sys/aliens/main.c](#), [examples/sys/singlestep/main.c](#), [examples/sys/start-with-exc/main.c](#), and [examples/sys/utcb-ipc/main.c](#).

Definition at line 956 of file [thread.h](#).

References [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:

**13.1.10.13.5 vCPU API**

vCPU API.

Collaboration diagram for vCPU API:

**Data Structures**

- struct [l4\\_vcpu\\_state\\_t](#)  
*State of a vCPU.*
- struct [l4\\_vcpu\\_regs\\_t](#)  
*vCPU registers.*
- struct [l4\\_vcpu\\_ipc\\_regs\\_t](#)  
*vCPU message registers.*

## Typedefs

- typedef struct l4\_vcpu\_state\_t **l4\_vcpu\_state\_t**  
*State of a vCPU.*
- typedef struct l4\_vcpu\_regs\_t **l4\_vcpu\_regs\_t**  
*vCPU registers.*
- typedef struct l4\_vcpu\_ipc\_regs\_t **l4\_vcpu\_ipc\_regs\_t**  
*vCPU message registers.*
- typedef [l4\\_exc\\_regs\\_t](#) **l4\_vcpu\_regs\_t**  
*vCPU registers.*
- typedef struct l4\_vcpu\_ipc\_regs\_t **l4\_vcpu\_ipc\_regs\_t**  
*vCPU message registers.*
- typedef struct l4\_vcpu\_regs\_t **l4\_vcpu\_regs\_t**  
*vCPU registers.*
- typedef struct l4\_vcpu\_ipc\_regs\_t **l4\_vcpu\_ipc\_regs\_t**  
*vCPU message registers.*
- typedef struct l4\_vcpu\_regs\_t **l4\_vcpu\_regs\_t**  
*vCPU registers.*
- typedef struct l4\_vcpu\_ipc\_regs\_t **l4\_vcpu\_ipc\_regs\_t**  
*vCPU message registers.*

## Enumerations

- enum [l4\\_vcpu\\_state\\_flags](#) {  
  [L4\\_VCPU\\_F\\_IRQ](#) = 0x01 , [L4\\_VCPU\\_F\\_PAGE\\_FAULTS](#) = 0x02 , [L4\\_VCPU\\_F\\_EXCEPTIONS](#) = 0x04 ,  
  [L4\\_VCPU\\_F\\_USER\\_MODE](#) = 0x20 ,  
  [L4\\_VCPU\\_F\\_FPU\\_ENABLED](#) = 0x80 }  
*State flags of a vCPU.*
- enum [l4\\_vcpu\\_sticky\\_flags](#) { [L4\\_VCPU\\_SF\\_IRQ\\_PENDING](#) = 0x01 }  
*Sticky flags of a vCPU.*
- enum [l4\\_vcpu\\_state\\_offset](#) { [L4\\_VCPU\\_OFFSET\\_EXT\\_STATE](#) = 0x180 , [L4\\_VCPU\\_OFFSET\\_EXT\\_INFOS](#) = 0x100 }  
*Offsets for vCPU state layouts.*
- enum [l4\\_vcpu\\_state\\_offset](#) { [L4\\_VCPU\\_OFFSET\\_EXT\\_STATE](#) = 0x280 , [L4\\_VCPU\\_OFFSET\\_EXT\\_INFOS](#) = 0x200 }  
*Offsets for vCPU state layouts.*
- enum [l4\\_vcpu\\_state\\_offset](#) { [L4\\_VCPU\\_OFFSET\\_EXT\\_STATE](#) = 0x400 , [L4\\_VCPU\\_OFFSET\\_EXT\\_INFOS](#) = 0x200 }  
*Offsets for vCPU state layouts.*
- enum [l4\\_vcpu\\_state\\_offset](#) { [L4\\_VCPU\\_OFFSET\\_EXT\\_STATE](#) = 0x400 , [L4\\_VCPU\\_OFFSET\\_EXT\\_INFOS](#) = 0x200 }  
*Offsets for vCPU state layouts.*

### 13.1.10.13.5.1 Detailed Description

vCPU API.

The vCPU API in [L4Re](#) implements virtual processors (vCPUs) on top of [L4::Thread](#). This API can be used for user level threading, operating system rehosting (see [L4Linux](#)) and virtualization.

You switch a thread into vCPU operation with [L4::Thread::vcpu\\_control](#).

In vCPU mode, incoming IPC can be redirected to a handler function. If an IPC is sent to the vCPU, the thread's normal execution is interrupted and the handler called. Which kind of IPC is redirected is specified by the [L4\\_vcpu\\_state\\_flags](#) set in the [l4\\_vcpu\\_state\\_t::state](#) field of [vcpu\\_state](#). All events enabled in the [vcpu\\_state](#) field are redirected to the handler. The handler is set via [l4\\_vcpu\\_state\\_t::entry\\_ip](#) and [l4\\_vcpu\\_state\\_t::entry\\_sp](#). IPC redirection works independent of "kernel" and "user" mode, but see [l4\\_vcpu\\_state\\_t::entry\\_sp](#). When the entry handler is called, the UTCB contains the result of the IPC and content normally found in CPU register is in [l4\\_vcpu\\_state\\_t::i](#).

Furthermore, the thread can execute in the context of different tasks, called the "kernel" and the "user" mode. The kernel task is the one to which the thread was originally bound via [L4::Thread::control\(\)](#). Execution starts in the kernel task and it is always switched to when the asynchronous IPC handler is invoked. When returning from the handler via [l4\\_thread\\_vcpu\\_resume\\_start\(\)](#) and [l4\\_thread\\_vcpu\\_resume\\_commit\(\)](#), a different user task can be specified by setting [l4\\_vcpu\\_state\\_t::user\\_task](#) and enabling the [L4\\_VCPU\\_F\\_USER\\_MODE](#) flag in [l4\\_vcpu\\_state\\_t::state](#). Note that the kernel may cache the user task internally, see [l4\\_thread\\_vcpu\\_resume\\_commit\(\)](#).

If the [L4\\_VCPU\\_F\\_USER\\_MODE](#) flag is enabled, the following flags will be automatically enabled in [l4\\_vcpu\\_state\\_t::state](#) on [L4::Thread::vcpu\\_resume\\_commit\(\)](#):

- [L4\\_VCPU\\_F\\_IRQ](#)
- [L4\\_VCPU\\_F\\_PAGE\\_FAULTS](#)
- [L4\\_VCPU\\_F\\_EXCEPTIONS](#)

When the kernel mode is entered, the following flags will be automatically disabled in [l4\\_vcpu\\_state\\_t::state](#):

- [L4\\_VCPU\\_F\\_IRQ](#)
- [L4\\_VCPU\\_F\\_PAGE\\_FAULTS](#)
- [L4\\_VCPU\\_F\\_USER\\_MODE](#)

Extended vCPU operation is used for hardware CPU virtualization. It can be enabled with [L4::Thread::vcpu\\_control\\_ext\(\)](#).

[vCPU Support Library](#) defines a convenience API for working with vCPUs.

See also

[vCPU Support Library](#)

### 13.1.10.13.5.2 Enumeration Type Documentation

#### L4\_vcpu\_state\_flags

```
enum L4_vcpu_state_flags
```

State flags of a vCPU.

#### Enumerator

L4_VCPU_F_IRQ	<p>Receiving of IRQs and IPC enabled. While this flag is not set, the corresponding vCPU thread will not receive any IPC and threads attempting to send an IPC to this thread will block (according to the selected send timeout).</p> <p><b>Note</b></p> <p>On <code>L4::Thread::vcpu_resume_commit()</code> this flag is automatically enabled in <code>l4_vcpu_state_t::state</code> if <code>L4_VCPU_F_USER_MODE</code> is enabled.</p> <p>When the kernel mode is entered, this flags is automatically disabled in <code>l4_vcpu_state_t::state</code>.</p>
L4_VCPU_F_PAGE_FAULTS	<p>Page faults enabled. If this flag is set, a page fault switches to kernel mode (potentially causing a VM exit) and calls the entry handler. If this flag is not set, a page fault generates a page fault IPC to the pager of the vCPU thread.</p> <p><b>Note</b></p> <p>IPC redirection for page faults controlled by this flag works independent of "kernel" and "user" mode.</p> <p>On <code>L4::Thread::vcpu_resume_commit()</code> this flag is automatically enabled in <code>l4_vcpu_state_t::state</code> if <code>L4_VCPU_F_USER_MODE</code> is enabled.</p> <p>When the kernel mode is entered, this flags is automatically disabled in <code>l4_vcpu_state_t::state</code>.</p>
L4_VCPU_F_EXCEPTIONS	<p>Exceptions enabled. If this flag is set, then, on the event of an exception, the vCPU switches to kernel mode (potentially causing a VM exit) and calls the entry handler. If this flag is not set, an exception generates an exception IPC to the exception handler of the vCPU thread.</p> <p><b>Note</b></p> <p>IPC redirection for exceptions controlled by this flag works independent of "kernel" and "user" mode.</p> <p>On <code>L4::Thread::vcpu_resume_commit()</code> this flag is automatically enabled in <code>l4_vcpu_state_t::state</code> if <code>L4_VCPU_F_USER_MODE</code> is enabled.</p>
L4_VCPU_F_USER_MODE	<p>User task will be used. If set, the vCPU switches to user mode on next <code>L4::Thread::vcpu_resume_commit()</code>. If clear, the vCPU stays in "kernel" mode.</p> <p><b>Note</b></p> <p>When the kernel mode is entered, this flags is automatically disabled in <code>l4_vcpu_state_t::state</code>.</p>

L4_VCPU_F_FPU_ENABLED	FPU enabled. This flag is only relevant if <a href="#">L4_VCPU_F_USER_MODE</a> is set. Setting this flag allows code in vCPU mode to use the FPU. IF this flag is not set, any FPU operation will trigger a corresponding exception (FPU fault).
-----------------------	--

Definition at line 101 of file [vcpu.h](#).

#### L4\_vcpu\_state\_offset [1/4]

enum [L4\\_vcpu\\_state\\_offset](#)

Offsets for vCPU state layouts.

##### Enumerator

L4_VCPU_OFFSET_EXT_STATE	Offset where extended state begins.
L4_VCPU_OFFSET_EXT_INFOS	Offset where extended infos begin.

Definition at line 34 of file [\\_\\_vcpu-arch.h](#).

#### L4\_vcpu\_state\_offset [2/4]

enum [L4\\_vcpu\\_state\\_offset](#)

Offsets for vCPU state layouts.

##### Enumerator

L4_VCPU_OFFSET_EXT_STATE	Offset where extended state begins.
L4_VCPU_OFFSET_EXT_INFOS	Offset where extended infos begin.

Definition at line 35 of file [\\_\\_vcpu-arch.h](#).

#### L4\_vcpu\_state\_offset [3/4]

enum [L4\\_vcpu\\_state\\_offset](#)

Offsets for vCPU state layouts.

##### Enumerator

L4_VCPU_OFFSET_EXT_STATE	Offset where extended state begins.
L4_VCPU_OFFSET_EXT_INFOS	Offset where extended infos begin.

Definition at line 36 of file [\\_\\_vcpu-arch.h](#).

**L4\_vcpu\_state\_offset** [4/4]

enum [L4\\_vcpu\\_state\\_offset](#)

Offsets for vCPU state layouts.

**Enumerator**

L4_VCPU_OFFSET_EXT_STATE	Offset where extended state begins.
L4_VCPU_OFFSET_EXT_INFOS	Offset where extended infos begin.

Definition at line [34](#) of file [\\_\\_vcpu-arch.h](#).

**L4\_vcpu\_sticky\_flags**

enum [L4\\_vcpu\\_sticky\\_flags](#)

Sticky flags of a vCPU.

**Enumerator**


L4_VCPU_SF_IRQ_PENDING	An event is pending: Either an IRQ or another thread attempts to send an IPC to this vCPU thread.
------------------------	---

Definition at line [167](#) of file [vcpu.h](#).

**13.1.10.14 Thread groups**

C thread group interface, see [L4::Thread\\_group](#) for the C++ interface.

Collaboration diagram for Thread groups:

**Functions**

- [l4\\_msgtag\\_t l4\\_thread\\_group\\_add](#) ([l4\\_cap\\_idx\\_t](#) tg, [l4\\_cap\\_idx\\_t](#) thread) [L4\\_NOTHROW](#)  
*Add thread to a thread group.*
- [l4\\_msgtag\\_t l4\\_thread\\_group\\_remove](#) ([l4\\_cap\\_idx\\_t](#) tg, [l4\\_cap\\_idx\\_t](#) thread) [L4\\_NOTHROW](#)  
*Remove thread from a thread group.*

### 13.1.10.14.1 Detailed Description

C thread group interface, see [L4::Thread\\_group](#) for the C++ interface.

An [L4](#) thread group is a collection of threads used as indirection for IPC gate and IRQ objects such that these objects can have multiple receivers, from which the kernel selects one according to a policy.

The primary use case for thread groups are multi-threaded servers and CPU core local IRQ / IPC delivery.

A thread can be bound to at most one thread group. Before binding a thread to a thread group, the thread must be bound to a task. All threads bound to the same thread group must belong to the same task.

### 13.1.10.14.2 Function Documentation

#### 13.1.10.14.2.1 l4\_thread\_group\_add()

```
l4_msgtag_t l4_thread_group_add (  
    l4_cap_idx_t tg,  
    l4_cap_idx_t thread) [inline]
```

Add thread to a thread group.

#### Parameters

<i>tg</i>	Thread group object.
<i>thread</i>	Thread to add to the thread group.

Definition at line 114 of file [thread\\_group.h](#).

References [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:



#### 13.1.10.14.2.2 l4\_thread\_group\_remove()

```
l4_msgtag_t l4_thread_group_remove (
    l4_cap_idx_t tg,
    l4_cap_idx_t thread) [inline]
```

Remove thread from a thread group.


##### Parameters

<i>tg</i>	Thread group object.
<i>thread</i>	Thread to remove from the thread group.

Definition at line 121 of file [thread\\_group.h](#).

References [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).


Here is the call graph for this function:



#### 13.1.10.15 Virtual Console

C Virtual console interface for simple character based input and output, see [L4::Vcon](#) for the C++ interface.

Collaboration diagram for Virtual Console:



##### Data Structures

- struct [l4\\_vcon\\_attr\\_t](#)  
*Vcon attribute structure.*



## Typedefs

- typedef struct l4\_vcon\_attr\_t l4\_vcon\_attr\_t  
*Vcon attribute structure.*

## Enumerations

- enum L4\_vcon\_size\_consts { L4\_VCON\_WRITE\_SIZE = (L4\_UTCB\_GENERIC\_DATA\_SIZE - 2) \* sizeof(l4\_umword\_t) , L4\_VCON\_READ\_SIZE = (L4\_UTCB\_GENERIC\_DATA\_SIZE - 1) \* sizeof(l4\_umword\_t) }  
*Size constants.*
- enum L4\_vcon\_i\_flags { L4\_VCON\_INLCR = 000100 , L4\_VCON\_IGNCR = 000200 , L4\_VCON\_ICRNL = 000400 }  
*Input flags.*
- enum L4\_vcon\_o\_flags { L4\_VCON\_ONLCR = 000004 , L4\_VCON\_OCRNL = 000010 , L4\_VCON\_ONLRET = 000040 }  
*Output flags.*
- enum L4\_vcon\_l\_flags { L4\_VCON\_ICANON = 000002 , L4\_VCON\_ECHO = 000010 }  
*Local flags.*

## Functions

- l4\_msgtag\_t l4\_vcon\_send (l4\_cap\_idx\_t vcon, char const \*buf, unsigned size) L4\_NOTHROW  
*Send data to virtual console.*
- l4\_msgtag\_t l4\_vcon\_send\_u (l4\_cap\_idx\_t vcon, char const \*buf, unsigned size, l4\_utcb\_t \*utcb) L4\_NOTHROW  
*Send data to *this* virtual console.*
- long l4\_vcon\_write (l4\_cap\_idx\_t vcon, char const \*buf, unsigned size) L4\_NOTHROW  
*Write data to virtual console.*
- long l4\_vcon\_write\_u (l4\_cap\_idx\_t vcon, char const \*buf, unsigned size, l4\_utcb\_t \*utcb) L4\_NOTHROW  
*Write data to *this* virtual console.*
- int l4\_vcon\_read (l4\_cap\_idx\_t vcon, char \*buf, unsigned size) L4\_NOTHROW  
*Read data from virtual console.*
- int l4\_vcon\_read\_u (l4\_cap\_idx\_t vcon, char \*buf, unsigned size, l4\_utcb\_t \*utcb) L4\_NOTHROW  
*Read data from *this* virtual console.*
- int l4\_vcon\_read\_with\_flags (l4\_cap\_idx\_t vcon, char \*buf, unsigned size) L4\_NOTHROW  
*Read data from virtual console, extended version including flags.*
- l4\_msgtag\_t l4\_vcon\_set\_attr (l4\_cap\_idx\_t vcon, l4\_vcon\_attr\_t const \*attr) L4\_NOTHROW  
*Set attributes of a Vcon.*
- l4\_msgtag\_t l4\_vcon\_set\_attr\_u (l4\_cap\_idx\_t vcon, l4\_vcon\_attr\_t const \*attr, l4\_utcb\_t \*utcb) L4\_NOTHROW  
*Set the attributes of *this* virtual console.*
- l4\_msgtag\_t l4\_vcon\_get\_attr (l4\_cap\_idx\_t vcon, l4\_vcon\_attr\_t \*attr) L4\_NOTHROW  
*Get attributes of a Vcon.*
- l4\_msgtag\_t l4\_vcon\_get\_attr\_u (l4\_cap\_idx\_t vcon, l4\_vcon\_attr\_t \*attr, l4\_utcb\_t \*utcb) L4\_NOTHROW  
*Get attributes of *this* virtual console.*
- void l4\_vcon\_set\_attr\_raw (l4\_vcon\_attr\_t \*attr) L4\_NOTHROW  
*Set terminal attributes to disable all special processing.*

### 13.1.10.15.1 Detailed Description

C Virtual console interface for simple character based input and output, see [L4::Vcon](#) for the C++ interface.

The interrupt for read events is provided by the virtual key interrupt which, in contrast to hardware IRQs, implements a limited functionality:

- Only IRQ line 0 is supported, no MSI vectors.
- The IRQ is edge-triggered and the IRQ mode cannot be changed.
- As the IRQ is edge-triggered, it does not have to be explicitly unmasked.

A server implementing the virtual console protocol has a queue for input events. When the first input event is added to the empty queue, the virtual key interrupt is triggered. Further events are added to the queue without generating further interrupts. The queue is emptied when a client reads all queued input events.

#### Include File

```
#include <l4/sys/vcon.h>
```

See [L4::Vcon](#) for the C++ interface.

### 13.1.10.15.2 Typedef Documentation

#### 13.1.10.15.2.1 l4\_vcon\_attr\_t

```
typedef struct l4_vcon_attr_t l4_vcon_attr_t
```

Vcon attribute structure.

The flags members can be a combination of their respective enums.

#### See also

[L4\\_vcon\\_i\\_flags](#)

[L4\\_vcon\\_o\\_flags](#)

[L4\\_vcon\\_l\\_flags](#)

### 13.1.10.15.3 Enumeration Type Documentation

#### 13.1.10.15.3.1 L4\_vcon\_i\_flags

enum [L4\\_vcon\\_i\\_flags](#)

Input flags.

##### Enumerator

L4_VCON_INLCR	Translate NL to CR.
L4_VCON_IGNCR	Ignore CR.
L4_VCON_ICRNL	Translate CR to NL if L4_VCON_IGNCR is not set.

Definition at line [208](#) of file [vcon.h](#).

#### 13.1.10.15.3.2 L4\_vcon\_l\_flags

enum [L4\\_vcon\\_l\\_flags](#)

Local flags.

##### Enumerator

L4_VCON_ICANON	Canonical mode.
L4_VCON_ECHO	Echo input.

Definition at line [230](#) of file [vcon.h](#).

#### 13.1.10.15.3.3 L4\_vcon\_o\_flags

enum [L4\\_vcon\\_o\\_flags](#)

Output flags.

##### Enumerator

L4_VCON_ONLCR	Translate NL to CR-NL.
L4_VCON_OCRNL	Translate CR to NL.
L4_VCON_ONLRET	Do not output CR.

Definition at line [219](#) of file [vcon.h](#).

### 13.1.10.15.3.4 L4\_vcon\_size\_consts

```
enum L4_vcon_size_consts
```

Size constants.

#### Enumerator

L4_VCON_WRITE_SIZE	Maximum size that can be written with one l4_vcon_write call.
L4_VCON_READ_SIZE	Maximum size that can be read with one l4_vcon_read* call.

Definition at line 95 of file [vcon.h](#).

### 13.1.10.15.4 Function Documentation

#### 13.1.10.15.4.1 l4\_vcon\_get\_attr()

```
l4_msgtag_t l4_vcon_get_attr (
    l4_cap_idx_t vcon,
    l4_vcon_attr_t * attr) [inline]
```

Get attributes of a Vcon.

#### Parameters

	<i>vcon</i>	Vcon object.
out	<i>attr</i>	Attribute structure.

#### Returns

Syscall return tag


#### Examples

[examples/sys/isr/main.c](#).

Definition at line 435 of file [vcon.h](#).

References [L4\\_NOTHROW](#), [l4\\_utcb\(\)](#), and [l4\\_vcon\\_get\\_attr\\_u\(\)](#).

Here is the call graph for this function:



13.1.10.15.4.2 `l4_vcon_get_attr_u()`

```
l4_msgtag_t l4_vcon_get_attr_u (
    l4_cap_idx_t vcon,
    l4_vcon_attr_t * attr,
    l4_utcb_t * utcb) [inline]
```

Get attributes of this virtual console.

**Parameters**

	<i>vcon</i>	Capability index of the vcon object.
out	<i>attr</i>	Attribute structure. Contains the attributes after a successful call of this function.
	<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. Defaults to <a href="#">l4_utcb</a> .

**Returns**


Syscall return tag.

Definition at line 417 of file [vcon.h](#).


References [l4\\_ipc\\_call\(\)](#), [L4\\_IPC\\_NEVER](#), [l4\\_msgtag\(\)](#), [L4\\_NOTHROW](#), [L4\\_PROTO\\_LOG](#), [L4\\_VCON\\_GET\\_ATTR\\_OP](#), and [l4\\_msg\\_regs\\_t::mr](#).

Referenced by [L4::Vcon::get\\_attr\(\)](#), and [l4\\_vcon\\_get\\_attr\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



#### 13.1.10.15.4.3 l4\_vcon\_read()

```
int l4_vcon_read (
    l4_cap_idx_t vcon,
    char * buf,
    unsigned size) [inline]
```

Read data from virtual console.

##### Parameters

	<i>vcon</i>	Vcon object.
out	<i>buf</i>	Pointer to data buffer.
	<i>size</i>	Size of buffer in bytes.

##### Return values

<code>-L4_EPERM</code>	Insufficient permissions; see precondition.
<code>&gt;size</code>	More bytes to read, <code>size</code> bytes are in the buffer <code>buf</code> .
<code>&lt;=size</code>	Number of bytes read.

##### Precondition

The capability `vcon` must have the permission `L4_CAP_FPAGE_W`.

##### Note

Size must not exceed `L4_VCON_READ_SIZE`.


##### Examples

[examples/sys/isr/main.c](#).

Definition at line 391 of file [vcon.h](#).

References [L4\\_NOTHROW](#), [l4\\_utcb\(\)](#), and [l4\\_vcon\\_read\\_u\(\)](#).

Here is the call graph for this function:



13.1.10.15.4.4 `l4_vcon_read_u()`

```
int l4_vcon_read_u (
    l4_cap_idx_t vcon,
    char * buf,
    unsigned size,
    l4_utcb_t * utcb) [inline]
```

Read data from this virtual console.

**Parameters**

	<i>vcon</i>	Capability index of the vcon object.
out	<i>buf</i>	Pointer to data buffer.
	<i>size</i>	Size of the data buffer in bytes.
	<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. Defaults to <a href="#">l4_utcb</a> .

**Return values**

<code>-L4_EPERM</code>	Insufficient permissions; see precondition.
<code>&gt;size</code>	More bytes to read, <code>size</code> bytes are in the buffer <code>buf</code> .
<code>&lt;=size</code>	Number of bytes read.

**Precondition**

The invoked Vcon capability must have the permission [L4\\_CAP\\_FPAGE\\_W](#).

**Note**


Size must not exceed [L4\\_VCON\\_READ\\_SIZE](#).

Definition at line 381 of file [vcon.h](#).

References [L4\\_NOTHROW](#), and [L4\\_VCON\\_READ\\_SIZE\\_MASK](#).

Referenced by [l4\\_vcon\\_read\(\)](#), and [L4::Vcon::read\(\)](#).

Here is the caller graph for this function:



#### 13.1.10.15.4.5 l4\_vcon\_read\_with\_flags()

```
int l4_vcon_read_with_flags (
    l4_cap_idx_t vcon,
    char * buf,
    unsigned size) [inline]
```

Read data from virtual console, extended version including flags.

##### Parameters

	<i>vcon</i>	Vcon object.
out	<i>buf</i>	Pointer to data buffer.
	<i>size</i>	Size of buffer in bytes.

If this function returns a positive value the caller can check the [L4\\_VCON\\_READ\\_STAT\\_BREAK](#) flag bit for a break condition. The bytes read can be obtained by masking the return value with [L4\\_VCON\\_READ\\_SIZE\\_MASK](#).

If a break condition is signaled, it is always the first event in the transmitted content, i.e. all characters supplied by this read call follow the break condition.

*buf* might be a NULL, in this case the input data will be dropped.

##### Note

Size must not exceed [L4\\_VCON\\_READ\\_SIZE](#).

##### Return values

<i>-L4_EPERM</i>	Insufficient permissions; see precondition.
<i>&gt;size</i>	More bytes to read, <i>size</i> bytes are in the buffer <i>buf</i> .
<i>&lt;=size</i>	Number of bytes read.

##### Precondition

The capability *vcon* must have the permission [L4\\_CAP\\_FPAGE\\_W](#).

Definition at line [375](#) of file [vcon.h](#).

References [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:





13.1.10.15.4.6 `l4_vcon_send()`

```
l4_msgtag_t l4_vcon_send (
    l4_cap_idx_t vcon,
    char const * buf,
    unsigned size) [inline]
```

Send data to virtual console.

**Parameters**

<i>vcon</i>	Vcon object.
<i>buf</i>	Pointer to data buffer.
<i>size</i>	Size of buffer in bytes.

**Returns**

Syscall return tag

**Note**

Size must not exceed `L4_VCON_WRITE_SIZE`, a proper value of the `size` parameter is NOT checked. Also, this function is a send only operation, this means there is no return value except for a failed send operation. Use `l4_ipc_error()` to check for send errors, and **do not** use `l4_error()`.


**Examples**

[examples/sys/utcb-ipc/main.c](#).

Definition at line 315 of file [vcon.h](#).

References [L4\\_NOTHROW](#), [l4\\_utcb\(\)](#), and [l4\\_vcon\\_send\\_u\(\)](#).

Here is the call graph for this function:



#### 13.1.10.15.4.7 l4\_vcon\_send\_u()

```
l4_msgtag_t l4_vcon_send_u (
    l4_cap_idx_t vcon,
    char const * buf,
    unsigned size,
    l4_utcb_t * utcb) [inline]
```

Send data to this virtual console.

##### Parameters

<i>vcon</i>	Capability index of the Vcon object.
<i>buf</i>	Pointer to the data buffer.
<i>size</i>	Size of the data buffer in bytes.
<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. Defaults to <a href="#">l4_utcb</a> .

##### Returns

Syscall return tag

##### Note


Size must not exceed [L4\\_VCON\\_WRITE\\_SIZE](#), a proper value of the `size` parameter is NOT checked. Also, this function is a send only operation, this means there is no return value except for a failed send operation. Use [l4\\_ipc\\_error\(\)](#) to check for send errors, do not use [l4\\_error\(\)](#), as [l4\\_error\(\)](#) will always return an error.

Definition at line [302](#) of file [vcon.h](#).


References [l4\\_bytes\\_to\\_mwords\(\)](#), [L4\\_IPC\\_NEVER](#), [l4\\_ipc\\_send\(\)](#), [l4\\_msgtag\(\)](#), [L4\\_MSGTAG\\_SCHEDULE](#), [L4\\_NOTHROW](#), [L4\\_PROTO\\_LOG](#), [L4\\_VCON\\_WRITE\\_OP](#), and [l4\\_msg\\_regs\\_t::mr](#).

Referenced by [l4\\_vcon\\_send\(\)](#), [l4\\_vcon\\_write\\_u\(\)](#), and [L4::Vcon::send\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



#### 13.1.10.15.4.8 l4\_vcon\_set\_attr()

```

l4_msgtag_t l4_vcon_set_attr (
    l4_cap_idx_t vcon,
    l4_vcon_attr_t const * attr) [inline]
  
```

Set attributes of a Vcon.

##### Parameters

<i>vcon</i>	Vcon object.
<i>attr</i>	Attribute structure.

##### Returns

Syscall return tag


##### Examples

[examples/sys/isr/main.c](#).

Definition at line 411 of file [vcon.h](#).

References [L4\\_NOTHROW](#), [l4\\_utcb\(\)](#), and [l4\\_vcon\\_set\\_attr\\_u\(\)](#).

Here is the call graph for this function:



#### 13.1.10.15.4.9 l4\_vcon\_set\_attr\_raw()

```
void l4_vcon_set_attr_raw (
    l4_vcon_attr_t * attr) [inline]
```

Set terminal attributes to disable all special processing.

Removes all flags that would mangle the read or written characters. Also disables echoing and any special processing of characters.

##### Parameters

<i>in, out</i>	<i>attr</i>	Attribute structure to update.
----------------	-------------	--------------------------------

Definition at line 441 of file [vcon.h](#).

References [L4\\_NOTHROW](#).

Referenced by [l4\\_vcon\\_attr\\_t::set\\_raw\(\)](#).

Here is the caller graph for this function:



#### 13.1.10.15.4.10 l4\_vcon\_set\_attr\_u()

```
l4_msgtag_t l4_vcon_set_attr_u (
    l4_cap_idx_t vcon,
    l4_vcon_attr_t const * attr,
    l4_utcb_t * utcb) [inline]
```

Set the attributes of `this` virtual console.

##### Parameters

<i>vcon</i>	Capability index of the vcon object.
<i>attr</i>	Attribute structure with the attributes for the virtual console.
<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. Defaults to <a href="#">l4_utcb</a> .

**Returns**


Syscall return tag.

Definition at line 397 of file [vcon.h](#).


References [l4\\_ipc\\_call\(\)](#), [L4\\_IPC\\_NEVER](#), [l4\\_msgtag\(\)](#), [L4\\_NOTHROW](#), [L4\\_PROTO\\_LOG](#), [L4\\_VCON\\_SET\\_ATTR\\_OP](#), and [l4\\_msg\\_regs\\_t::mr](#).

Referenced by [l4\\_vcon\\_set\\_attr\(\)](#), and [L4::Vcon::set\\_attr\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:

**13.1.10.15.4.11 l4\_vcon\_write()**

```

long l4_vcon_write (
    l4_cap_idx_t vcon,
    char const * buf,
    unsigned size) [inline]
  
```

Write data to virtual console.

**Parameters**

<i>vcon</i>	Vcon object.
<i>buf</i>	Pointer to data buffer.
<i>size</i>	Size of buffer in bytes.


### Return values

$<0$	Error.
$\geq 0$	Number of bytes written to the virtual console

Definition at line 336 of file [vcon.h](#).

References [L4\\_NOTHROW](#), [l4\\_utcb\(\)](#), and [l4\\_vcon\\_write\\_u\(\)](#).

Here is the call graph for this function:



#### 13.1.10.15.4.12 l4\_vcon\_write\_u()

```

long l4_vcon_write_u (
    l4_cap_idx_t vcon,
    char const * buf,
    unsigned size,
    l4_utcb_t * utcb) [inline]

```

Write data to `this` virtual console.

### Parameters

<i>vcon</i>	Capability index of the vcon object.
<i>buf</i>	Pointer to the data buffer.
<i>size</i>	Size of the data buffer in bytes.
<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. Defaults to <a href="#">l4_utcb</a> .

### Return values


$< 0$	Error.
$\geq 0$	Number of bytes written to the virtual console.

Definition at line 321 of file [vcon.h](#).


References [l4\\_error\(\)](#), [l4\\_msgtag\\_has\\_error\(\)](#), [L4\\_NOTHROW](#), [l4\\_vcon\\_send\\_u\(\)](#), and [L4\\_VCON\\_WRITE\\_SIZE](#).

Referenced by [l4\\_vcon\\_write\(\)](#), and [L4::Vcon::write\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 13.1.11 Kernel Interface Page

Kernel Interface Page.

Collaboration diagram for Kernel Interface Page:



## Topics

- [Memory descriptors \(C version\)](#) . . . . . 432  
*C Interface for KIP memory descriptors.*

## Data Structures

- class [L4::Kip::Mem\\_desc](#)  
*Memory descriptors stored in the kernel interface page.*
- struct [l4\\_kernel\\_info\\_t](#)  
[L4](#) Kernel Interface Page.

## Macros

- `#define L4_KERNEL_INFO_MAGIC (0x4BE6344CL) /* "L4μK" */`  
*Kernel Info Page identifier ("L4μK").*

## Typedefs

- typedef struct [l4\\_kernel\\_info\\_t](#) [l4\\_kernel\\_info\\_t](#)  
[L4](#) Kernel Interface Page.

## Enumerations

- enum { [L4\\_KIP\\_OFFS\\_READ\\_US](#) = 0x900 , [L4\\_KIP\\_OFFS\\_READ\\_NS](#) = 0x980 }

## Functions

- [l4\\_kernel\\_info\\_t](#) const \* [l4\\_kip](#) (void) [L4\\_NOTHROW](#)  
*Get Kernel Info Page.*
- [l4\\_umword\\_t](#) [l4\\_kip\\_version](#) ([l4\\_kernel\\_info\\_t](#) const \*kip) [L4\\_NOTHROW](#)  
*Get the kernel version.*
- const char \* [l4\\_kip\\_version\\_string](#) ([l4\\_kernel\\_info\\_t](#) const \*kip) [L4\\_NOTHROW](#)  
*Get the kernel version string.*
- int [l4\\_kernel\\_info\\_version\\_offset](#) ([l4\\_kernel\\_info\\_t](#) const \*kip) [L4\\_NOTHROW](#)  
*Return offset in bytes of version\_strings relative to the KIP base.*
- [l4\\_cpu\\_time\\_t](#) [l4\\_kip\\_clock](#) ([l4\\_kernel\\_info\\_t](#) const \*kip) [L4\\_NOTHROW](#)  
*Return clock value from the KIP.*
- [l4\\_umword\\_t](#) [l4\\_kip\\_clock\\_lw](#) ([l4\\_kernel\\_info\\_t](#) const \*kip) [L4\\_NOTHROW](#)  
*Return least significant machine word of clock value from the KIP.*
- [l4\\_uint64\\_t](#) [l4\\_kip\\_clock\\_ns](#) ([l4\\_kernel\\_info\\_t](#) const \*kip) [L4\\_NOTHROW](#)  
*Return current clock using the KIP in nanoseconds.*



### 13.1.11.1 Detailed Description

Kernel Interface Page.

C interface for the Kernel Interface Page:

C++ interface for the Kernel Interface Page:

#### Include File

```
#include <l4/sys/kip>
```

#### Include File

```
#include <l4/sys/kip.h>
```

### 13.1.11.2 Typedef Documentation

#### 13.1.11.2.1 l4\_kernel\_info\_t

```
typedef struct l4_kernel_info_t l4_kernel_info_t
```

[L4 Kernel Interface Page](#).

32-bit architecture may assume that the upper 32 bits of addresses is 0

### 13.1.11.3 Enumeration Type Documentation

#### 13.1.11.3.1 anonymous enum

```
anonymous enum
```

#### Enumerator

L4_KIP_OFFS_READ_US	Offset of KIP code (provided by the kernel) for reading the KIP clock in microseconds. If the kernel is configured for a fine-grained KIP clock (CONFIG_SYNC↔TSC enabled for IA32, ARM_SYNC_CLOCK for ARM), this code provides the KIP clock with microseconds granularity and accuracy by reading the hardware clock used by the kernel and transforming this value into microseconds. Otherwise this code just reads the KIP clock value.
L4_KIP_OFFS_READ_NS	Offset of KIP code (provided by the kernel) for reading the time stamp counter and transforming this value into nanoseconds. If the kernel is configured for fine-grained KIP clock (CONFIG_SYNC enabled for IA32, ARM_SYNC_CLOCK for ARM), this code provides the KIP clock with nanoseconds granularity and accuracy by reading the hardware clock used by the kernel and transforming this value into nanoseconds. Otherwise this code just reads the KIP clock value and multiplies it by 1000.

Definition at line 95 of file [kip.h](#).

### 13.1.11.4 Function Documentation

#### 13.1.11.4.1 l4\_kernel\_info\_version\_offset()

```
int l4_kernel_info_version_offset (
    l4_kernel_info_t const * kip) [inline]
```

Return offset in bytes of version\_strings relative to the KIP base.

##### Parameters

<i>kip</i>	Pointer to the kernel info page (KIP).
------------	--

##### Returns


offset of version\_strings relative to the KIP base address, in bytes.

Definition at line 238 of file [kip.h](#).

References [L4\\_NOTHROW](#).

Referenced by [l4\\_kip\\_version\\_string\(\)](#).

Here is the caller graph for this function:



#### 13.1.11.4.2 l4\_kip()

```
l4_kernel_info_t const * l4_kip (
    void ) [inline]
```

Get Kernel Info Page.

##### Returns


Pointer to Kernel Info Page (KIP) structure.

Definition at line 226 of file [kip.h](#).

References [L4\\_NOTHROW](#).

Referenced by [l4re\\_kip\(\)](#).

Here is the caller graph for this function:



#### 13.1.11.4.3 l4\_kip\_clock()

```
l4_cpu_time_t l4_kip_clock (
    l4_kernel_info_t const * kip) [inline]
```

Return clock value from the KIP.

##### Parameters

<i>kip</i>	Pointer to the kernel info page (KIP).
------------	--

##### Returns

Value of the clock field in the KIP.

The KIP clock always contains the current (relative) time in micro seconds independently of the CPU frequency. The clock is only guaranteed to be accurate within the scheduling granularity announced in the KIP.

This function basically calls the KIP code for reading the KIP clock with microseconds resolution. The accuracy depends on the platform and the kernel configuration.

##### See also

[L4\\_KIP\\_OFFS\\_READ\\_US](#).

##### Examples


[examples/libs/shmc/prodcons.c](#).

Definition at line 242 of file [kip.h](#).

References [L4\\_KIP\\_OFFS\\_READ\\_US](#), and [L4\\_NOTHROW](#).

Referenced by [l4\\_kip\\_clock\\_lw\(\)](#), [L4::Poll\\_timeout\\_kipclock::set\(\)](#), and [L4::Poll\\_timeout\\_kipclock::test\(\)](#).

Here is the caller graph for this function:



#### 13.1.11.4.4 l4\_kip\_clock\_lw()

```
l4_umword_t l4_kip_clock_lw (
    l4_kernel_info_t const * kip) [inline]
```

Return least significant machine word of clock value from the KIP.

##### Parameters

<i>kip</i>	Pointer to the kernel info page (KIP).
------------	--

##### Returns

Lower machine word of clock value from the KIP.

**Deprecated** Use [l4\\_kip\\_clock\(\)](#) instead.

This function will always provide the least significant machine word of the clock value from the KIP, regardless of the kernel configuration.

Definition at line 261 of file [kip.h](#).

References [l4\\_kip\\_clock\(\)](#), and [L4\\_NOTHROW](#).

Here is the call graph for this function:



#### 13.1.11.4.5 l4\_kip\_clock\_ns()

```
l4_cpu_time_t l4_kip_clock_ns (
    l4_kernel_info_t const * kip) [inline]
```

Return current clock using the KIP in nanoseconds.

##### Parameters

<i>kip</i>	Pointer to the kernel info page (KIP).
------------	--

##### Returns

Value of the current clock in nanoseconds.

This function basically calls the KIP code for reading the KIP clock with nanoseconds resolution. The accuracy depends on the platform and the kernel configuration.

##### See also

[L4\\_KIP\\_OFFS\\_READ\\_NS](#).

Definition at line 252 of file [kip.h](#).

References [L4\\_KIP\\_OFFS\\_READ\\_NS](#), and [L4\\_NOTHROW](#).

#### 13.1.11.4.6 l4\_kip\_version()

```
l4_umword_t l4_kip_version (
    l4_kernel_info_t const * kip) [inline]
```

Get the kernel version.

##### Parameters

<i>kip</i>	Kernel Info Page.
------------	-------------------

##### Returns

Kernel version string. 0 if KIP could not be mapped.

Definition at line 230 of file [kip.h](#).

References [L4\\_NOTHROW](#).

#### 13.1.11.4.7 l4\_kip\_version\_string()

```
const char * l4_kip_version_string (
    l4_kernel_info_t const * kip) [inline]
```

Get the kernel version string.

##### Parameters

<i>kip</i>	Kernel Info Page.
------------	-------------------

##### Returns


Kernel version string.

Definition at line 234 of file [kip.h](#).

References [l4\\_kernel\\_info\\_version\\_offset\(\)](#), and [L4\\_NOTHROW](#).

Referenced by [l4\\_kip\\_kernel\\_has\\_feature\(\)](#).

Here is the call graph for this function:




Here is the caller graph for this function:



### 13.1.11.5 Memory descriptors (C version)

C Interface for KIP memory descriptors.

Collaboration diagram for Memory descriptors (C version):



### Data Structures

- struct `l4_kernel_info_mem_desc_t`  
*Memory descriptor data structure.*

### Typedefs

- typedef struct `l4_kernel_info_mem_desc_t` `l4_kernel_info_mem_desc_t`  
*Memory descriptor data structure.*

### Enumerations

- enum `l4_mem_type_t` {  
`l4_mem_type_undefined` = 0x0 , `l4_mem_type_conventional` = 0x1 , `l4_mem_type_reserved` = 0x2 ,  
`l4_mem_type_dedicated` = 0x3 ,  
`l4_mem_type_shared` = 0x4 , `l4_mem_type_info` = 0xd , `l4_mem_type_bootloader` = 0xe , `l4_mem_type_archspecific`  
= 0xf }  
*Type of a memory descriptor.*
- enum `l4_mem_info_sub_type_t` { `l4_mem_info_acpi_rsdp` = 0 , `l4_mem_reserved_kernel` = 0 ,  
`l4_mem_reserved_heap` = 1 , `l4_mem_reserved_mmio` = 2 }  
*Memory sub types for l4\_mem\_type\_info descriptors.*
- enum `l4_mem_archspecific_sub_type_common_t` { `l4_mem_archspecific_acpi_tables` = 3 , `l4_mem_archspecific_acpi_nvs`  
= 4 }  
*Memory sub types for l4\_mem\_type\_archspecific descriptors.*

## Functions

- `l4_kernel_info_mem_desc_t * l4_kernel_info_get_mem_descs (l4_kernel_info_t *kip) L4_NOTHROW`  
*Get pointer to memory descriptors from KIP.*
- `unsigned l4_kernel_info_get_num_mem_descs (l4_kernel_info_t *kip) L4_NOTHROW`  
*Get number of memory descriptors in KIP.*
- `void l4_kernel_info_set_mem_desc (l4_kernel_info_mem_desc_t *md, l4_addr_t start, l4_addr_t end, unsigned type, unsigned virt, unsigned sub_type) L4_NOTHROW`  
*Populate a memory descriptor.*
- `l4_umword_t l4_kernel_info_get_mem_desc_start (l4_kernel_info_mem_desc_t *md) L4_NOTHROW`  
*Get start address of the region described by the memory descriptor.*
- `l4_umword_t l4_kernel_info_get_mem_desc_end (l4_kernel_info_mem_desc_t *md) L4_NOTHROW`  
*Get end address of the region described by the memory descriptor.*
- `l4_umword_t l4_kernel_info_get_mem_desc_type (l4_kernel_info_mem_desc_t *md) L4_NOTHROW`  
*Get type of the memory region.*
- `l4_umword_t l4_kernel_info_get_mem_desc_subtype (l4_kernel_info_mem_desc_t *md) L4_NOTHROW`  
*Get sub-type of memory region.*
- `l4_umword_t l4_kernel_info_get_mem_desc_is_virtual (l4_kernel_info_mem_desc_t *md) L4_NOTHROW`  
*Get virtual flag of the memory descriptor.*

### 13.1.11.5.1 Detailed Description

C Interface for KIP memory descriptors.

#### Include File

```
#include <l4/sys/memdesc.h>
```

This module contains the C functions to access the memory descriptor in the kernel interface page (KIP).

### 13.1.11.5.2 Typedef Documentation

#### 13.1.11.5.2.1 l4\_kernel\_info\_mem\_desc\_t

```
typedef struct l4_kernel_info_mem_desc_t l4_kernel_info_mem_desc_t
```

Memory descriptor data structure.

#### Note

This data type is opaque, and must be accessed by the accessor functions defined in this module.

### 13.1.11.5.3 Enumeration Type Documentation

#### 13.1.11.5.3.1 I4\_mem\_archspecific\_sub\_type\_common\_t

```
enum I4_mem_archspecific_sub_type_common_t
```

Memory sub types for I4\_mem\_type\_archspecific descriptors.

##### Enumerator

I4_mem_archspecific_acpi_tables	Firmware ACPI tables.
I4_mem_archspecific_acpi_nvs	Firmware reserved address space.

Definition at line 63 of file [memdesc.h](#).

#### 13.1.11.5.3.2 I4\_mem\_info\_sub\_type\_t

```
enum I4_mem_info_sub_type_t
```

Memory sub types for I4\_mem\_type\_info descriptors.

##### Enumerator

I4_mem_info_acpi_rsdp	Physical address of the ACPI root pointer.
I4_mem_reserved_kernel	Kernel image.
I4_mem_reserved_heap	Kernel heap.
I4_mem_reserved_mmio	MMIO range reserved by kernel.

Definition at line 50 of file [memdesc.h](#).

#### 13.1.11.5.3.3 I4\_mem\_type\_t

```
enum I4_mem_type_t
```

Type of a memory descriptor.

##### Enumerator

I4_mem_type_undefined	Undefined, unused descriptor.
I4_mem_type_conventional	Conventional memory.
I4_mem_type_reserved	Reserved memory for kernel etc.
I4_mem_type_dedicated	Dedicated memory (some device memory).
I4_mem_type_shared	Shared memory (not implemented).
I4_mem_type_info	Info from the boot loader.
I4_mem_type_bootloader	Memory owned by the boot loader.



<code>l4_mem_type_archspecific</code>	Architecture specific memory (e.g., ACPI memory).
---------------------------------------	---

Definition at line 33 of file [memdesc.h](#).

#### 13.1.11.5.4 Function Documentation

##### 13.1.11.5.4.1 `l4_kernel_info_get_mem_desc_end()`

```
l4_umword_t l4_kernel_info_get_mem_desc_end (
    l4_kernel_info_mem_desc_t * md) [inline]
```

Get end address of the region described by the memory descriptor.

##### Returns

End address.

Definition at line 219 of file [memdesc.h](#).

References [L4\\_NOTHROW](#).

##### 13.1.11.5.4.2 `l4_kernel_info_get_mem_desc_is_virtual()`

```
l4_umword_t l4_kernel_info_get_mem_desc_is_virtual (
    l4_kernel_info_mem_desc_t * md) [inline]
```

Get virtual flag of the memory descriptor.

##### Returns

1 if region is virtual memory, 0 if region is physical memory

Definition at line 240 of file [memdesc.h](#).

References [L4\\_NOTHROW](#).

##### 13.1.11.5.4.3 `l4_kernel_info_get_mem_desc_start()`

```
l4_umword_t l4_kernel_info_get_mem_desc_start (
    l4_kernel_info_mem_desc_t * md) [inline]
```

Get start address of the region described by the memory descriptor.

##### Returns

Start address.

Definition at line 212 of file [memdesc.h](#).

References [L4\\_NOTHROW](#).

#### 13.1.11.5.4.4 l4\_kernel\_info\_get\_mem\_desc\_subtype()

```
l4_umword_t l4_kernel_info_get_mem_desc_subtype (  
    l4_kernel_info_mem_desc_t * md) [inline]
```

Get sub-type of memory region.

##### Returns

Sub-type.

The sub type is defined for architecture specific memory descriptors (see [l4\\_mem\\_type\\_archspecific](#)) and has architecture specific meaning.

Definition at line 233 of file [memdesc.h](#).

References [L4\\_NOTHROW](#).

#### 13.1.11.5.4.5 l4\_kernel\_info\_get\_mem\_desc\_type()

```
l4_umword_t l4_kernel_info_get_mem_desc_type (  
    l4_kernel_info_mem_desc_t * md) [inline]
```

Get type of the memory region.

##### Returns

Type of the region (see [l4\\_mem\\_type\\_t](#)).

Definition at line 226 of file [memdesc.h](#).

References [L4\\_NOTHROW](#).

#### 13.1.11.5.4.6 l4\_kernel\_info\_get\_num\_mem\_descs()

```
unsigned l4_kernel_info_get_num_mem_descs (  
    l4_kernel_info_t * kip) [inline]
```

Get number of memory descriptors in KIP.

##### Returns

Number of memory descriptors.

Definition at line 190 of file [memdesc.h](#).

References [L4\\_NOTHROW](#).

#### 13.1.11.5.4.7 l4\_kernel\_info\_set\_mem\_desc()

```
void l4_kernel_info_set_mem_desc (
    l4_kernel_info_mem_desc_t * md,
    l4_addr_t start,
    l4_addr_t end,
    unsigned type,
    unsigned virt,
    unsigned sub_type) [inline]
```

Populate a memory descriptor.

##### Parameters

<i>md</i>	Pointer to memory descriptor
<i>start</i>	Start of region
<i>end</i>	End of region
<i>type</i>	Type of region
<i>virt</i>	1 if virtual region, 0 if physical region
<i>sub_type</i>	Sub type.

Definition at line 197 of file [memdesc.h](#).

References [L4\\_NOTHROW](#).

## 13.1.12 Capabilities

C interface for capabilities.

Collaboration diagram for Capabilities:



### Macros

- **#define L4\_CAP\_SHIFT**  
*Capability index shift.*
- **#define L4\_CAP\_OFFSET**  
*Offset of two consecutive capability selectors.*
- **#define L4\_CAP\_MASK**  
*Mask to get only the relevant bits of an [l4\\_cap\\_idx\\_t](#).*

## Typedefs

- typedef unsigned long [l4\\_cap\\_idx\\_t](#)  
*Capability selector type.*

## Enumerations

- enum [l4\\_default\\_caps\\_t](#) {  
[L4\\_BASE\\_TASK\\_CAP](#) , [L4\\_BASE\\_FACTORY\\_CAP](#) , [L4\\_BASE\\_THREAD\\_CAP](#) , [L4\\_BASE\\_PAGER\\_CAP](#) ,  
[L4\\_BASE\\_LOG\\_CAP](#) , [L4\\_BASE\\_ICU\\_CAP](#) , [L4\\_BASE\\_SCHEDULER\\_CAP](#) , [L4\\_BASE\\_IOMMU\\_CAP](#) ,  
[L4\\_BASE\\_DEBUGGER\\_CAP](#) , [L4\\_BASE\\_ARM\\_SMCCC\\_CAP](#) , [L4\\_BASE\\_CAPS\\_LAST\\_P1](#) , [L4\\_BASE\\_CAPS\\_LAST](#)  
= [L4\\_BASE\\_CAPS\\_LAST\\_P1](#) - 1 }  
*Default capabilities setup for the initial tasks.*

## Functions

- unsigned [l4\\_is\\_invalid\\_cap](#) ([l4\\_cap\\_idx\\_t](#) c) [L4\\_NOTHROW](#)  
*Test if a capability selector is the invalid capability.*
- unsigned [l4\\_is\\_valid\\_cap](#) ([l4\\_cap\\_idx\\_t](#) c) [L4\\_NOTHROW](#)  
*Test if a capability selector is a valid selector.*
- unsigned [l4\\_capability\\_equal](#) ([l4\\_cap\\_idx\\_t](#) c1, [l4\\_cap\\_idx\\_t](#) c2) [L4\\_NOTHROW](#)  
*Test if the capability indices of two capability selectors are equal.*

### 13.1.12.1 Detailed Description

C interface for capabilities.

Add

```
#include <l4/sys/types.h>
#include <l4/sys/consts.h>
```

to your code to use the functions and definitions explained here.

### 13.1.12.2 Typedef Documentation

#### 13.1.12.2.1 [l4\\_cap\\_idx\\_t](#)

```
typedef unsigned long l4\_cap\_idx\_t
```

Capability selector type.

A capability selector is either a (shifted) capability index or the invalid capability selector [L4\\_INVALID\\_CAP](#).

Usage of the invalid capability selector is defined only for invoking IPC (see [Object Invocation](#)): When IPC is invoked on [L4\\_INVALID\\_CAP](#), then it is resolved to a capability for the current thread with full permissions.

Otherwise, the API assumes that each argument of type [l4\\_cap\\_idx\\_t](#) is a capability index, i.e., `idx << L4\_CAP\_SHIFT` for arbitrary `idx`. The behavior for other arguments is then undefined.

## Examples

[examples/libs/shmc/prodcons.c](#), [examples/sys/aliens/main.c](#), [examples/sys/isr/main.c](#), [examples/sys/singlestep/main.c](#), [examples/sys/start-with-exc/main.c](#), and [examples/sys/utcb-ipc/main.c](#).

Definition at line 352 of file [types.h](#).

### 13.1.12.3 Enumeration Type Documentation

#### 13.1.12.3.1 l4\_default\_caps\_t

```
enum l4_default_caps_t
```

Default capabilities setup for the initial tasks.

These capability selectors are setup per default by the micro kernel for the two initial tasks, the Root-Pager (Sigma0) and the Root-Task (Moe).

#### Attention

These constants do not have any particular meaning for applications started by Moe, see [Initial Environment](#) for this kind of information.

#### See also

[Initial Environment](#) for information useful for normal user applications.

#### Enumerator

L4_BASE_TASK_CAP	Capability selector for the current task.
L4_BASE_FACTORY_CAP	Capability selector for the factory.
L4_BASE_THREAD_CAP	Capability selector for the first thread.
L4_BASE_PAGER_CAP	Capability selector for the pager gate. For Sigma0, the pager is not present since it never raises page faults. For Moe, the pager is set to Sigma0.
L4_BASE_LOG_CAP	Capability selector for the log object. Present if the corresponding feature is turned on in the microkernel configuration.
L4_BASE_ICU_CAP	Capability selector for the base icu object.
L4_BASE_SCHEDULER_CAP	Capability selector for the scheduler cap.
L4_BASE_IOMMU_CAP	Capability selector for the IO-MMU cap. Present if the microkernel detected an IO-MMU.
L4_BASE_DEBUGGER_CAP	Capability selector for the debugger cap. Present if the corresponding feature is turned on in the microkernel configuration.
L4_BASE_ARM_SMCCC_CAP	Capability selector for the ARM SMCCC cap. Present if the microkernel detected an ARM SMC capable trusted execution environment.
L4_BASE_CAPS_LAST	Last capability index used for base capabilities.

Definition at line 322 of file [consts.h](#).

### 13.1.12.4 Function Documentation

#### 13.1.12.4.1 l4\_capability\_equal()

```
unsigned l4_capability_equal (
    l4_cap_idx_t c1,
    l4_cap_idx_t c2) [inline]
```

Test if the capability indices of two capability selectors are equal.

#### Parameters

<i>c1</i>	Capability selector.
<i>c2</i>	Capability selector.

#### Return values

0	The index parts of the capability selectors differ.
1	The index parts of the capability selectors are equal.

#### Precondition

Both capability selectors must be valid (cf. [l4\\_is\\_valid\\_cap\(\)](#)) otherwise the return value is undefined.

Definition at line 413 of file [types.h](#).

References [L4\\_CAP\\_SHIFT](#), and [L4\\_NOTHROW](#).

#### 13.1.12.4.2 l4\_is\_invalid\_cap()

```
unsigned l4_is_invalid_cap (
    l4_cap_idx_t c) [inline]
```

Test if a capability selector is the invalid capability.

#### Parameters

<i>c</i>	Capability selector
----------	---------------------

#### Return values

0	The capability selector is not the invalid capability.
>0	The capability selector is the invalid capability.

#### Examples

[examples/libs/l4re/c/ma+rm.c](#), [examples/sys/aliens/main.c](#), [examples/sys/isr/main.c](#), [examples/sys/singlestep/main.c](#), [examples/sys/start-with-exc/main.c](#), and [examples/sys/utcb-ipc/main.c](#).

Definition at line 405 of file [types.h](#).

References [L4\\_NOTHROW](#).

#### 13.1.12.4.3 l4\_is\_valid\_cap()

```
unsigned l4_is_valid_cap (
    l4_cap_idx_t c) [inline]
```

Test if a capability selector is a valid selector.

##### Parameters

<i>c</i>	Capability selector
----------	---------------------

##### Return values


0	The capability selector is not valid.
>0	The capability selector is valid.

Definition at line 409 of file [types.h](#).

References [L4\\_NOTHROW](#).

Referenced by [L4Re::Util::Cap\\_alloc\\_base::free\(\)](#), and [L4Re::Util::Counting\\_cap\\_alloc< COUNTERTYPE, Dbg >::free\(\)](#).


Here is the caller graph for this function:



#### 13.1.13 Memory Operations

Operations for memory access.

Collaboration diagram for Memory Operations:



## Enumerations

- enum [L4\\_mem\\_op\\_widths](#) { [L4\\_MEM\\_WIDTH\\_1BYTE](#) = 0 , [L4\\_MEM\\_WIDTH\\_2BYTE](#) = 1 , [L4\\_MEM\\_WIDTH\\_4BYTE](#) = 2 }

*Memory access width definitions.*

## Functions

- unsigned long [l4\\_mem\\_read](#) (unsigned long virtaddress, unsigned width)  
*Read user task memory from kernel privilege level.*
- void [l4\\_mem\\_write](#) (unsigned long virtaddress, unsigned width, unsigned long value)  
*Write user task memory from kernel privilege level.*

### 13.1.13.1 Detailed Description

Operations for memory access.

This module provides functionality to access user task memory from the kernel. This is needed for some devices that are only accessible from privileged processor mode. Only use this when absolutely required. This functionality is only available on the ARM architecture.

```
#include <l4/sys/mem_op.h>
```

### 13.1.13.2 Enumeration Type Documentation

#### 13.1.13.2.1 L4\_mem\_op\_widths

```
enum L4\_mem\_op\_widths
```

Memory access width definitions.

#### Enumerator

<a href="#">L4_MEM_WIDTH_1BYTE</a>	Access one byte (8-bit width).
<a href="#">L4_MEM_WIDTH_2BYTE</a>	Access two bytes (16-bit width).
<a href="#">L4_MEM_WIDTH_4BYTE</a>	Access four bytes (32-bit width).

Definition at line [40](#) of file [mem\\_op.h](#).



### 13.1.13.3 Function Documentation

#### 13.1.13.3.1 l4\_mem\_read()

```
unsigned long l4_mem_read (  
    unsigned long virtaddress,  
    unsigned width)    [inline]
```

Read user task memory from kernel privilege level.

##### Parameters

<i>virtaddress</i>	Virtual address in the calling task.
<i>width</i>	Width of access in bytes in log2,

##### See also

[L4\\_mem\\_op\\_widths](#)

##### Returns

Read value.

Upon an given invalid address or invalid width value the function does nothing.

Definition at line 130 of file [mem\\_op.h](#).

References [l4\\_mem\\_arm\\_op\\_call\(\)](#).

Here is the call graph for this function:



#### 13.1.13.3.2 l4\_mem\_write()

```
void l4_mem_write (  
    unsigned long virtaddress,  
    unsigned width,  
    unsigned long value)    [inline]
```

Write user task memory from kernel privilege level.

### Parameters


<i>virtaddress</i>	Virtual address in the calling task.
<i>width</i>	Width of access in bytes in log2 (i.e. allowed values: 0, 1, 2)
<i>value</i>	Value to write.

Upon an given invalid address or invalid width value the function does nothing.

Definition at line 136 of file [mem\\_op.h](#).


References [l4\\_mem\\_arm\\_op\\_call\(\)](#).

Here is the call graph for this function:



### 13.1.14 Integer Types

Collaboration diagram for Integer Types:



### Files

- file [l4int.h](#)  
*Fixed sized integer types, generic version.*
- file [l4int.h](#)  
*Fixed sized integer types, arm version.*
- file [l4int.h](#)  
*Fixed sized integer types, arm version.*
- file [l4int.h](#)  
*Fixed sized integer types, AMD64 version.*
- file [l4int.h](#)  
*Fixed sized integer types, x86 version.*

## Macros

- `#define L4_MWORD_BITS 32`  
*Size of machine words in bits.*
- `#define L4_MWORD_BITS 64`  
*Size of machine words in bits.*
- `#define L4_MWORD_BITS 64`  
*Size of machine words in bits.*
- `#define L4_MWORD_BITS 32`  
*Size of machine words in bits.*

## Typedefs

- `typedef signed char l4_int8_t`  
*Signed 8bit value.*
- `typedef unsigned char l4_uint8_t`  
*Unsigned 8bit value.*
- `typedef signed short int l4_int16_t`  
*Signed 16bit value.*
- `typedef unsigned short int l4_uint16_t`  
*Unsigned 16bit value.*
- `typedef signed int l4_int32_t`  
*Signed 32bit value.*
- `typedef unsigned int l4_uint32_t`  
*Unsigned 32bit value.*
- `typedef signed long long l4_int64_t`  
*Signed 64bit value.*
- `typedef unsigned long long l4_uint64_t`  
*Unsigned 64bit value.*
- `typedef unsigned long l4_addr_t`  
*Address type.*
- `typedef signed long l4_mword_t`  
*Signed machine word.*
- `typedef unsigned long l4_umword_t`  
*Unsigned machine word.*
- `typedef l4_uint64_t l4_cpu_time_t`  
*CPU clock type.*
- `typedef l4_uint64_t l4_kernel_clock_t`  
*Kernel clock type.*
- `typedef unsigned int l4_size_t`  
*Unsigned size type.*
- `typedef signed int l4_ssize_t`  
*Signed size type.*
- `typedef unsigned long l4_size_t`  
*Unsigned size type.*
- `typedef signed long l4_ssize_t`  
*Signed size type.*
- `typedef unsigned long l4_size_t`  
*Unsigned size type.*
- `typedef signed long l4_ssize_t`  
*Signed size type.*
- `typedef unsigned int l4_size_t`  
*Unsigned size type.*
- `typedef signed int l4_ssize_t`  
*Signed size type.*

### 13.1.14.1 Detailed Description

#### Include File

```
#include <l4/sys/l4int.h>
```

## 13.2 EDID parsing functionality

### Enumerations

- enum [Libedid\\_consts](#) { [Libedid\\_block\\_size](#) = 128 }  
*EDID constants.*

### Functions

- int [libedid\\_check\\_header](#) (const unsigned char \*edid)  
*Check for valid EDID header.*
- int [libedid\\_checksum](#) (const unsigned char \*edid)  
*Calculates the EDID checksum.*
- unsigned [libedid\\_version](#) (const unsigned char \*edid)  
*Returns the EDID version number.*
- unsigned [libedid\\_revision](#) (const unsigned char \*edid)  
*Returns the EDID revision number.*
- void [libedid\\_pnp\\_id](#) (const unsigned char \*edid, unsigned char \*id)  
*Extracts the display's PnP ID.*
- void [libedid\\_preferred\\_resolution](#) (const unsigned char \*edid, unsigned \*w, unsigned \*h)  
*Extract the display's preferred mode.*
- unsigned [libedid\\_num\\_ext\\_blocks](#) (const unsigned char \*edid)  
*Get the number of EDID extension blocks.*
- unsigned [libedid\\_dump\\_standard\\_timings](#) (const unsigned char \*edid)  
*Dump the standard timings to stdout.*
- void [libedid\\_dump](#) (const unsigned char \*edid)  
*Dump raw EDID data to stdout.*

### 13.2.1 Detailed Description

### 13.2.2 Enumeration Type Documentation

#### 13.2.2.1 Libedid\_consts

```
enum Libedid\_consts
```

EDID constants.

#### Enumerator

---

<code>Libedid_block_size</code>	Size of one EDID block in bytes.
---------------------------------	----------------------------------

Definition at line 23 of file [edid.h](#).

### 13.2.3 Function Documentation

#### 13.2.3.1 `libedid_check_header()`

```
int libedid_check_header (  
    const unsigned char * edid)
```

Check for valid EDID header.

##### Parameters

<i>edid</i>	Pointer to a 128byte EDID block
-------------	---------------------------------

##### Returns

0 if the header is correct, -EINVAL otherwise

#### 13.2.3.2 `libedid_checksum()`

```
int libedid_checksum (  
    const unsigned char * edid)
```

Calculates the EDID checksum.

##### Parameters

<i>edid</i>	Pointer to a 128byte EDID block
-------------	---------------------------------

##### Returns

0 if checksum is correct, -EINVAL otherwise

### 13.2.3.3 libedid\_dump()

```
void libedid_dump (
    const unsigned char * edid)
```

Dump raw EDID data to stdout.

#### Parameters

<i>edid</i>	Pointer to a 128byte EDID block
-------------	---------------------------------

### 13.2.3.4 libedid\_dump\_standard\_timings()

```
unsigned libedid_dump_standard_timings (
    const unsigned char * edid)
```

Dump the standard timings to stdout.

#### Parameters

<i>edid</i>	Pointer to a 128byte EDID block
-------------	---------------------------------

#### Returns

Number of standard timings stored in EDID

### 13.2.3.5 libedid\_num\_ext\_blocks()

```
unsigned libedid_num_ext_blocks (
    const unsigned char * edid)
```

Get the number of EDID extension blocks.

#### Parameters

<i>edid</i>	Pointer to a 128byte EDID block
-------------	---------------------------------

#### Returns

Number of EDID extension blocks

### 13.2.3.6 libedid\_pnp\_id()

```
void libedid_pnp_id (
    const unsigned char * edid,
    unsigned char * id)
```

Extracts the display's PnP ID.

#### Parameters

	<i>edid</i>	Pointer to a 128byte EDID block
out	<i>id</i>	Return the PnP id. Must point to 4 bytes.

### 13.2.3.7 libedid\_preferred\_resolution()

```
void libedid_preferred_resolution (
    const unsigned char * edid,
    unsigned * w,
    unsigned * h)
```

Extract the display's preferred mode.

#### Parameters

	<i>edid</i>	Pointer to a 128byte EDID block
out	<i>w</i>	X resolution of preferred video mode in pixels.
out	<i>h</i>	Y resolution of preferred video mode in pixels.

### 13.2.3.8 libedid\_revision()

```
unsigned libedid_revision (
    const unsigned char * edid)
```

Returns the EDID revision number.

#### Parameters

<i>edid</i>	Pointer to a 128 EDID block
-------------	-----------------------------

#### Returns

Revision number

### 13.2.3.9 libedid\_version()

```
unsigned libedid_version (
    const unsigned char * edid)
```

Returns the EDID version number.

#### Parameters

<i>edid</i>	Pointer to a 128byte EDID block
-------------	---------------------------------

#### Returns

Version number

## 13.3 IO interface

#### Typedefs

- typedef [l4vbus\\_resource\\_t](#) [l4io\\_resource\\_t](#)  
*Resource descriptor.*
- typedef [l4vbus\\_device\\_t](#) [l4io\\_device\\_t](#)  
*Device descriptor.*

#### Enumerations

- enum [l4io\\_iomem\\_flags\\_t](#) {  
[L4IO\\_MEM\\_NONCACHED](#) = 0 , [L4IO\\_MEM\\_CACHED](#) = 1 , [L4IO\\_MEM\\_USE\\_MTRR](#) = 2 , [L4IO\\_MEM\\_ATTR\\_MASK](#) = 0xf ,  
[L4IO\\_MEM\\_WRITE\\_COMBINED](#) = [L4IO\\_MEM\\_USE\\_MTRR](#) | [L4IO\\_MEM\\_CACHED](#) , [L4IO\\_MEM\\_USE\\_RESERVED\\_AREA](#) = 0x40 << 8 , [L4IO\\_MEM\\_EAGER\\_MAP](#) = 0x80 << 8 }  
*Flags for IO memory.*
- enum [l4io\\_device\\_types\\_t](#) {  
[L4IO\\_DEVICE\\_INVALID](#) = 0 , [L4IO\\_DEVICE\\_PCI](#) , [L4IO\\_DEVICE\\_USB](#) , [L4IO\\_DEVICE\\_OTHER](#) ,  
[L4IO\\_DEVICE\\_ANY](#) = ~0 }  
*Device types.*
- enum [l4io\\_resource\\_types\\_t](#) {  
[L4IO\\_RESOURCE\\_INVALID](#) = [L4VBUS\\_RESOURCE\\_INVALID](#) , [L4IO\\_RESOURCE\\_IRQ](#) = [L4VBUS\\_RESOURCE\\_IRQ](#) , [L4IO\\_RESOURCE\\_MEM](#) = [L4VBUS\\_RESOURCE\\_MEM](#) , [L4IO\\_RESOURCE\\_PORT](#) = [L4VBUS\\_RESOURCE\\_PORT](#) ,  
[L4IO\\_RESOURCE\\_ANY](#) = ~0 }  
*Resource types.*



## Functions

- long [l4io\\_request\\_iomem](#) ([l4\\_addr\\_t](#) phys, unsigned long size, int flags, [l4\\_addr\\_t](#) \*virt)  
*Request an IO memory region.*
- long [l4io\\_request\\_iomem\\_region](#) ([l4\\_addr\\_t](#) phys, [l4\\_addr\\_t](#) virt, unsigned long size, int flags)  
*Request an IO memory region and map it to a specified region.*
- long [l4io\\_release\\_iomem](#) ([l4\\_addr\\_t](#) virt, unsigned long size)  
*Release an IO memory region.*
- long [l4io\\_request\\_ioport](#) (unsigned portnum, unsigned len)  
*Request an IO port region.*
- long [l4io\\_release\\_ioport](#) (unsigned portnum, unsigned len)  
*Release an IO port region.*
- int [l4io\\_lookup\\_device](#) (const char \*devname, [l4io\\_device\\_handle\\_t](#) \*dev\_handle, [l4io\\_device\\_t](#) \*dev, [l4io\\_resource\\_handle\\_t](#) \*res\_handle)  
*Find a device by name.*
- int [l4io\\_lookup\\_resource](#) ([l4io\\_device\\_handle\\_t](#) devhandle, enum [l4io\\_resource\\_types\\_t](#) type, [l4io\\_resource\\_handle\\_t](#) \*reshandle, [l4io\\_resource\\_t](#) \*res)  
*Request a specific resource from a device description.*
- [l4\\_addr\\_t](#) [l4io\\_request\\_resource\\_iomem](#) ([l4io\\_device\\_handle\\_t](#) devhandle, [l4io\\_resource\\_handle\\_t](#) \*reshandle)  
*Request IO memory.*
- int [l4io\\_has\\_resource](#) (enum [l4io\\_resource\\_types\\_t](#) type, [l4vbus\\_paddr\\_t](#) start, [l4vbus\\_paddr\\_t](#) end)  
*Check if a resource is available.*

### 13.3.1 Detailed Description

### 13.3.2 Typedef Documentation

#### 13.3.2.1 [l4io\\_resource\\_t](#)

```
typedef l4vbus\_resource\_t l4io\_resource\_t
```

Resource descriptor.

For IRQ types, the end field is not used, i.e. only a single interrupt can be described with a [l4io\\_resource\\_t](#)

Definition at line 67 of file [types.h](#).

### 13.3.3 Enumeration Type Documentation

#### 13.3.3.1 [l4io\\_device\\_types\\_t](#)

```
enum l4io\_device\_types\_t
```

Device types.

## Enumerator

L4IO_DEVICE_INVALID	Invalid type.
L4IO_DEVICE_PCI	PCI device.
L4IO_DEVICE_USB	USB device.
L4IO_DEVICE_OTHER	Any other device without unique IDs.
L4IO_DEVICE_ANY	any type

Definition at line 36 of file [types.h](#).

### 13.3.3.2 l4io\_iomem\_flags\_t

enum [l4io\\_iomem\\_flags\\_t](#)

Flags for IO memory.

#### Enumerator

L4IO_MEM_NONCACHED	Non-cache memory.
L4IO_MEM_CACHED	Cache memory.
L4IO_MEM_USE_MTRR	Use MTRR.
L4IO_MEM_USE_RESERVED_AREA	Use reserved area for mapping I/O memory. Flag only valid for <a href="#">l4io_request_iomem_region()</a>
L4IO_MEM_EAGER_MAP	Eagerly map the I/O memory. Passthrough to the l4re-rm.

Definition at line 14 of file [types.h](#).

### 13.3.3.3 l4io\_resource\_types\_t

enum [l4io\\_resource\\_types\\_t](#)

Resource types.

#### Enumerator

L4IO_RESOURCE_INVALID	Invalid type.
L4IO_RESOURCE_IRQ	Interrupt resource.
L4IO_RESOURCE_MEM	I/O memory resource.
L4IO_RESOURCE_PORT	I/O port resource (x86 only).
L4IO_RESOURCE_ANY	any type

Definition at line 48 of file [types.h](#).

### 13.3.4 Function Documentation

#### 13.3.4.1 l4io\_has\_resource()

```
int l4io_has_resource (
    enum l4io_resource_types_t type,
    l4vbus_paddr_t start,
    l4vbus_paddr_t end)
```

Check if a resource is available.

##### Parameters

<i>type</i>	Type of resource
<i>start</i>	Minimal value.
<i>end</i>	Maximum value.

References [L4\\_INLINE](#).

#### 13.3.4.2 l4io\_lookup\_device()

```
int l4io_lookup_device (
    const char * devname,
    l4io_device_handle_t * dev_handle,
    l4io_device_t * dev,
    l4io_resource_handle_t * res_handle)
```

Find a device by name.

##### Parameters

	<i>devname</i>	Name of device.
out	<i>dev_handle</i>	Device handle for found device, can be NULL.
out	<i>dev</i>	Device information, filled by the function, can be NULL.
out	<i>res_handle</i>	Resource handle, can be NULL.

##### Returns

0 on success, error code otherwise

References [L4\\_CV](#), and [L4\\_EXPORT](#).

### 13.3.4.3 l4io\_lookup\_resource()

```
int l4io_lookup_resource (
    l4io_device_handle_t devhandle,
    enum l4io_resource_types_t type,
    l4io_resource_handle_t * reshandle,
    l4io_resource_t * res)
```

Request a specific resource from a device description.

#### Parameters

	<i>devhandle</i>	Device handle.
	<i>type</i>	Type of resource to request (see <a href="#">l4io_resource_types_t</a> ).
in, out	<i>reshandle</i>	Resource handle, start with handle returned by device functions. The next resource handle is returned here.
out	<i>res</i>	Device descriptor.

#### Returns

0 on success, error code otherwise, esp. -L4\_ENOENT if no more resources found

References [L4\\_CV](#), and [L4\\_EXPORT](#).

### 13.3.4.4 l4io\_release\_iomem()

```
long l4io_release_iomem (
    l4_addr_t virt,
    unsigned long size)
```

Release an IO memory region.

#### Parameters

<i>virt</i>	Virtual address of region to free, see <a href="#">l4io_request_iomem</a>
<i>size</i>	Size of the region to release.

#### Returns

0 on success, <0 on error

References [L4\\_CV](#), and [L4\\_EXPORT](#).

#### 13.3.4.5 `l4io_release_ioport()`

```
long l4io_release_ioport (
    unsigned portnum,
    unsigned len)
```

Release an IO port region.

##### Parameters

<i>portnum</i>	Start of port range to release
<i>len</i>	Length of range to request

##### Returns

0 on success, <0 on error

##### Note

X86 architecture only

References [L4\\_CV](#), [L4\\_EXPORT](#), and [L4\\_INLINE](#).

#### 13.3.4.6 `l4io_request_iomem()`

```
long l4io_request_iomem (
    l4_addr_t phys,
    unsigned long size,
    int flags,
    l4_addr_t * virt)
```

Request an IO memory region.

##### Parameters

	<i>phys</i>	Physical address of the I/O memory region
	<i>size</i>	Size of the region in Bytes, granularity pages.
	<i>flags</i>	See <a href="#">l4io_iomem_flags_t</a>
<i>in, out</i>	<i>virt</i>	Virtual address where the IO memory region should be mapped to. If the caller passes '0' a region in the caller's address space is searched and the virtual address is returned.

##### Return values

0	Success.
-L4_ENOENT	No area in the caller's address space could be found to map the IO memory region.
-L4_EPERM	Operation not allowed.
-L4_EINVAL	Invalid value.

<code>-L4_EADDRNOTAVAIL</code>	The requested virtual address is not available.
<code>-L4_ENOMEM</code>	The requested IO memory region could not be allocated.
<code>&lt;0</code>	IPC errors.

**Note**

This function uses [L4Re](#) functionality to reserve a part of the virtual address space of the caller.

References [L4\\_CV](#), and [L4\\_EXPORT](#).

**13.3.4.7 l4io\_request\_iomem\_region()**

```
long l4io_request_iomem_region (
    l4_addr_t phys,
    l4_addr_t virt,
    unsigned long size,
    int flags)
```

Request an IO memory region and map it to a specified region.

**Parameters**

<i>phys</i>	Physical address of the I/O memory region
<i>virt</i>	Virtual address.
<i>size</i>	Size of the region in Bytes, granularity pages.
<i>flags</i>	See <a href="#">l4io_iomem_flags_t</a>

**Return values**

<code>0</code>	Success.
<code>-L4_ENOENT</code>	No area could be found to map the IO memory region.
<code>-L4_EPERM</code>	Operation not allowed.
<code>-L4_EINVAL</code>	Invalid value.
<code>-L4_EADDRNOTAVAIL</code>	The requested virtual address is not available.
<code>-L4_ENOMEM</code>	The requested IO memory region could not be allocated.
<code>&lt;0</code>	IPC errors.

**Note**

This function uses [L4Re](#) functionality to reserve a part of the virtual address space of the caller.

References [L4\\_CV](#), and [L4\\_EXPORT](#).

#### 13.3.4.8 l4io\_request\_ioport()

```
long l4io_request_ioport (
    unsigned portnum,
    unsigned len)
```

Request an IO port region.

##### Parameters

<i>portnum</i>	Start of port range to request
<i>len</i>	Length of range to request

##### Returns

0 on success, <0 on error

##### Note

X86 architecture only

References [L4\\_CV](#), and [L4\\_EXPORT](#).

#### 13.3.4.9 l4io\_request\_resource\_iomem()

```
l4_addr_t l4io_request_resource_iomem (
    l4io_device_handle_t devhandle,
    l4io_resource_handle_t * reshandle)
```

Request IO memory.

##### Parameters

	<i>devhandle</i>	Device handle.
<i>in, out</i>	<i>reshandle</i>	Resource handle from which IO memory should be requested. Upon successful completion 'reshandle' points to the device's next resource.

##### Return values

0	An error occurred. The value of 'reshandle' is undefined.
>0	The virtual address of the IO memory mapping.

References [L4\\_CV](#), and [L4\\_EXPORT](#).

## 13.4 IPC Helpers

### Functions

- void [L4::throw\\_ipc\\_exception](#) ([L4::Cap](#)< void > const &o, [l4\\_msgtag\\_t](#) const &err, [l4\\_utcb\\_t](#) \*utcb)  
*Throw an [L4](#) IPC error as exception.*
- void [L4::throw\\_ipc\\_exception](#) (void const \*o, [l4\\_msgtag\\_t](#) const &err, [l4\\_utcb\\_t](#) \*utcb)  
*Throw an [L4](#) IPC error as exception.*

### 13.4.1 Detailed Description

### 13.4.2 Function Documentation

#### 13.4.2.1 throw\_ipc\_exception() [1/2]

```
void L4::throw_ipc_exception (
    L4::Cap< void > const & o,
    l4\_msgtag\_t const & err,
    l4\_utcb\_t * utcb) [inline]
```

Throw an [L4](#) IPC error as exception.

#### Parameters


<i>o</i>	The client side object, for which the IPC was invoked.
<i>err</i>	The IPC result code (error code).
<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. See <a href="#">l4_utcb</a> .

Definition at line [34](#) of file [ipc\\_helper](#).

References [l4\\_msgtag\\_t::has\\_error\(\)](#).

Referenced by [throw\\_ipc\\_exception\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:





### 13.4.2.2 throw\_ipc\_exception() [2/2]

```
void L4::throw_ipc_exception (
    void const * o,
    l4_msgtag_t const & err,
    l4_utcb_t * utcb) [inline]
```

Throw an [L4](#) IPC error as exception.

#### Parameters

<i>o</i>	The client side object, for which the IPC was invoked.
<i>err</i>	The IPC result code (error code).
<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. See <a href="#">l4_utcb</a> .

Definition at line 50 of file [ipc\\_helper](#).


References [throw\\_ipc\\_exception\(\)](#).

Here is the call graph for this function:



## 13.5 IRQ handling library

Collaboration diagram for IRQ handling library:




#### Topics

- Interface using direct functionality. . . . . [460](#)
- Interface for asynchronous ISR handlers. . . . . [467](#)  
*This interface has just two (main) functions.*

### 13.5.1 Detailed Description

### 13.5.2 Interface using direct functionality.

Collaboration diagram for Interface using direct functionality.:



### Topics

- Interface using direct functionality. . . . . 465

### Functions

- `l4irq_t * l4irq_attach (int irqnum)`  
*Attach/connect to IRQ.*
- `l4irq_t * l4irq_attach_ft (int irqnum, unsigned mode)`  
*Attach/connect to IRQ using given type.*
- `l4irq_t * l4irq_attach_thread (int irqnum, l4_cap_idx_t to_thread)`  
*Attach/connect to IRQ.*
- `l4irq_t * l4irq_attach_thread_ft (int irqnum, l4_cap_idx_t to_thread, unsigned mode)`  
*Attach/connect to IRQ using given type.*
- `long l4irq_wait (l4irq_t *irq)`  
*Wait for specified IRQ.*
- `long l4irq_unmask_and_wait_any (l4irq_t *unmask_irq, l4irq_t **ret_irq)`  
*Unmask a specific IRQ and wait for any attached IRQ.*
- `long l4irq_wait_any (l4irq_t **irq)`  
*Wait for any attached IRQ.*
- `long l4irq_unmask (l4irq_t *irq)`  
*Unmask a specific IRQ.*
- `long l4irq_detach (l4irq_t *irq)`  
*Detach from IRQ.*

### 13.5.2.1 Detailed Description

### 13.5.2.2 Function Documentation

#### 13.5.2.2.1 l4irq\_attach()

```
l4irq_t * l4irq_attach (  
    int irqnum)
```

Attach/connect to IRQ.

##### Parameters

<i>irqnum</i>	IRQ number to request
---------------	-----------------------

##### Returns

Pointer to l4irq\_t structure, 0 on error

This l4irq\_attach has to be called in the same thread as l4irq\_wait and caller has to be a pthread thread.

##### Examples

[examples/libs/libirq/loop.c](#).

References [L4\\_CV](#).

#### 13.5.2.2.2 l4irq\_attach\_ft()

```
l4irq_t * l4irq_attach_ft (  
    int irqnum,  
    unsigned mode)
```

Attach/connect to IRQ using given type.

##### Parameters

<i>irqnum</i>	IRQ number to request
<i>mode</i>	Interrupt type,

##### See also

[L4\\_irq\\_mode](#)

##### Returns

Pointer to l4irq\_t structure, 0 on error

This l4irq\_attach has to be called in the same thread as l4irq\_wait and caller has to be a pthread thread.

References [L4\\_CV](#).

### 13.5.2.2.3 l4irq\_attach\_thread()

```
l4irq_t * l4irq_attach_thread (
    int irqnum,
    l4_cap_idx_t to_thread)
```

Attach/connect to IRQ.

#### Parameters

<i>irqnum</i>	IRQ number to request
<i>to_thread</i>	Attach IRQ to this specified thread.

#### Returns

Pointer to l4irq\_t structure, 0 on error

The pointer to the IRQ structure is used as a label in the IRQ object.

References [L4\\_CV](#).

### 13.5.2.2.4 l4irq\_attach\_thread\_ft()

```
l4irq_t * l4irq_attach_thread_ft (
    int irqnum,
    l4_cap_idx_t to_thread,
    unsigned mode)
```

Attach/connect to IRQ using given type.

#### Parameters

<i>irqnum</i>	IRQ number to request
<i>to_thread</i>	Attach IRQ to this specified thread.
<i>mode</i>	Interrupt type,

#### See also

[L4\\_irq\\_mode](#)

#### Returns

Pointer to l4irq\_t structure, 0 on error

The pointer to the IRQ structure is used as a label in the IRQ object.

References [L4\\_CV](#).

#### 13.5.2.2.5 l4irq\_detach()

```
long l4irq_detach (  
    l4irq_t * irq)
```

Detach from IRQ.

##### Parameters

<i>irq</i>	IRQ data structure
------------	--------------------

##### Returns

0 on success, != 0 on error

References [L4\\_CV](#).

#### 13.5.2.2.6 l4irq\_unmask()

```
long l4irq_unmask (  
    l4irq_t * irq)
```

Unmask a specific IRQ.

##### Parameters

<i>irq</i>	IRQ data structure
------------	--------------------

##### Returns

0 on success, != 0 on error

This function is useful if a thread wants to wait for multiple IRQs using `l4_ipc_wait`.

References [L4\\_CV](#).

#### 13.5.2.2.7 l4irq\_unmask\_and\_wait\_any()

```
long l4irq_unmask_and_wait_any (  
    l4irq_t * unmask_irq,  
    l4irq_t ** ret_irq)
```

Unmask a specific IRQ and wait for any attached IRQ.

##### Parameters

	<i>unmask_irq</i>	IRQ data structure for unmask.
--	-------------------	--------------------------------

out	<i>ret_irq</i>	Received interrupt.
-----	----------------	---------------------

**Returns**

0 on success, != 0 on error

References [L4\\_CV](#).

**13.5.2.2.8 l4irq\_wait()**

```
long l4irq_wait (
    l4irq_t * irq)
```

Wait for specified IRQ.

**Parameters**

<i>irq</i>	IRQ data structure
------------	--------------------

**Returns**

0 on success, != 0 on error

**Examples**

[examples/libs/libirq/loop.c](#).

References [L4\\_CV](#).

**13.5.2.2.9 l4irq\_wait\_any()**

```
long l4irq_wait_any (
    l4irq_t ** irq)
```

Wait for any attached IRQ.

**Return values**

<i>irq</i>	Received interrupt.
------------	---------------------


**Returns**

0 on success, != 0 on error

References [L4\\_CV](#).

### 13.5.2.3 Interface using direct functionality.

Collaboration diagram for Interface using direct functionality.:



## Functions

- `l4irq_t * l4irq_attach_cap (l4_cap_idx_t irqcap)`  
*Attach/connect to IRQ.*
- `l4irq_t * l4irq_attach_cap_ft (l4_cap_idx_t irqcap, unsigned mode)`  
*Attach/connect to IRQ using given type.*
- `l4irq_t * l4irq_attach_thread_cap (l4_cap_idx_t irqcap, l4_cap_idx_t to_thread)`  
*Attach/connect to IRQ.*
- `l4irq_t * l4irq_attach_thread_cap_ft (l4_cap_idx_t irqcap, l4_cap_idx_t to_thread, unsigned mode)`  
*Attach/connect to IRQ using given type.*

#### 13.5.2.3.1 Detailed Description

#### 13.5.2.3.2 Function Documentation

##### 13.5.2.3.2.1 l4irq\_attach\_cap()

```
l4irq_t * l4irq_attach_cap (
    l4_cap_idx_t irqcap)
```

Attach/connect to IRQ.

#### Parameters

<code>irqcap</code>	IRQ capability
---------------------	----------------

#### Returns

Pointer to `l4irq_t` structure, 0 on error

This `l4irq_attach` has to be called in the same thread as `l4irq_wait` and caller has to be a pthread thread.

References [L4\\_CV](#).

### 13.5.2.3.2.2 l4irq\_attach\_cap\_ft()

```
l4irq_t * l4irq_attach_cap_ft (
    l4_cap_idx_t irqcap,
    unsigned mode)
```

Attach/connect to IRQ using given type.

#### Parameters

<i>irqcap</i>	IRQ capability
<i>mode</i>	Interrupt type,

See also

[L4\\_irq\\_mode](#)

#### Returns

Pointer to l4irq\_t structure, 0 on error

This l4irq\_attach has to be called in the same thread as l4irq\_wait and caller has to be a pthread thread.

References [L4\\_CV](#).

### 13.5.2.3.2.3 l4irq\_attach\_thread\_cap()

```
l4irq_t * l4irq_attach_thread_cap (
    l4_cap_idx_t irqcap,
    l4_cap_idx_t to_thread)
```

Attach/connect to IRQ.

#### Parameters

<i>irqcap</i>	IRQ capability
<i>to_thread</i>	Attach IRQ to this thread.

#### Returns

Pointer to l4irq\_t structure, 0 on error

The pointer to the IRQ structure is used as a label in the IRQ object.

References [L4\\_CV](#).



#### 13.5.2.3.2.4 l4irq\_attach\_thread\_cap\_ft()

```
l4irq_t * l4irq_attach_thread_cap_ft (
    l4_cap_idx_t irqcap,
    l4_cap_idx_t to_thread,
    unsigned mode)
```

Attach/connect to IRQ using given type.

##### Parameters

<i>irqcap</i>	IRQ capability
<i>to_thread</i>	Attach IRQ to this thread.
<i>mode</i>	Interrupt type,

##### See also

[L4\\_irq\\_mode](#)

##### Returns

Pointer to l4irq\_t structure, 0 on error


The pointer to the IRQ structure is used as a label in the IRQ object.

References [L4\\_CV](#).

### 13.5.3 Interface for asynchronous ISR handlers.

This interface has just two (main) functions.

Collaboration diagram for Interface for asynchronous ISR handlers.:



##### Topics

- [Interface for asynchronous ISR handlers with a given IRQ capability.](#) . . . . . 469  
*This group is just an enhanced version to [l4irq\\_request\(\)](#) which takes a capability object instead of a plain number.*

## Functions

- `l4irq_t * l4irq_request` (int irqnum, void(\*isr\_handler)(void \*), void \*isr\_data, int irq\_thread\_prio, unsigned mode)  
*Attach asynchronous ISR handler to IRQ.*
- `long l4irq_release` (l4irq\_t \*irq)  
*Release asynchronous ISR handler and free resources.*

### 13.5.3.1 Detailed Description

This interface has just two (main) functions.

`l4irq_request` to install a handler for an interrupt and `l4irq_release` to uninstall the handler again and release all resources associated with it.

### 13.5.3.2 Function Documentation

#### 13.5.3.2.1 `l4irq_release()`

```
long l4irq_release (
    l4irq_t * irq)
```

Release asynchronous ISR handler and free resources.

#### Parameters

<i>irq</i>	IRQ data structure
------------	--------------------

#### Returns

0 success, != 0 failure

#### Examples

[examples/libs/libirq/async\\_isr.c](#).

References [L4\\_CV](#).

**13.5.3.2.2 l4irq\_request()**

```
l4irq_t * l4irq_request (
    int irqnum,
    void(* isr_handler ) (void *),
    void * isr_data,
    int irq_thread_prio,
    unsigned mode)
```

Attach asynchronous ISR handler to IRQ.

**Parameters**

<i>irqnum</i>	IRQ number to request
<i>isr_handler</i>	Handler routine that is called when an interrupt triggers
<i>isr_data</i>	Pointer given as argument to isr_handler
<i>irq_thread_prio</i>	L4 thread priority of the ISR handler. Give -1 for same priority as creator.
<i>mode</i>	Interrupt type,

**See also**

[L4\\_irq\\_mode](#)

**Returns**

Pointer to l4irq\_t structure, 0 on error

**Examples**


[examples/libs/libirq/async\\_isr.c](#).

References [L4\\_CV](#).

**13.5.3.3 Interface for asynchronous ISR handlers with a given IRQ capability.**

This group is just an enhanced version to [l4irq\\_request\(\)](#) which takes a capability object instead of a plain number.

Collaboration diagram for Interface for asynchronous ISR handlers with a given IRQ capability.:



## Functions

- `l4irq_t * l4irq_request_cap (l4_cap_idx_t irqcap, void(*isr_handler)(void *), void *isr_data, int irq_thread_prio, unsigned mode)`

*Attach asynchronous ISR handler to IRQ.*

### 13.5.3.3.1 Detailed Description

This group is just an enhanced version to `l4irq_request()` which takes a capability object instead of a plain number.

### 13.5.3.3.2 Function Documentation

#### 13.5.3.3.2.1 l4irq\_request\_cap()

```
l4irq_t * l4irq_request_cap (
    l4_cap_idx_t irqcap,
    void(* isr_handler ) (void *),
    void * isr_data,
    int irq_thread_prio,
    unsigned mode)
```

Attach asynchronous ISR handler to IRQ.

## Parameters

<i>irqcap</i>	IRQ capability
<i>isr_handler</i>	Handler routine that is called when an interrupt triggers
<i>isr_data</i>	Pointer given as argument to <i>isr_handler</i>
<i>irq_thread_prio</i>	L4 thread priority of the ISR handler. Give -1 for same priority as creator.
<i>mode</i>	Interrupt type,

## See also

[L4\\_irq\\_mode](#)

## Returns

Pointer to `l4irq_t` structure, 0 on error

## 13.6 L4 IPC Opcodes

List of protocol specific opcodes used for communication with [L4Re](#) and Kernel objects.

## Enumerations

- enum `L4_icu_opcode` {  
`L4_ICU_OP_BIND` , `L4_ICU_OP_UNBIND` , `L4_ICU_OP_INFO` , `L4_ICU_OP_MSI_INFO` ,  
`L4_ICU_OP_UNMASK` , `L4_ICU_OP_MASK` , `L4_ICU_OP_SET_MODE` }  
*Opcodes to the ICU interface.*
- enum `L4_ipc_gate_ops` { `L4_IPC_GATE_BIND_OP` = 0x10 , `L4_IPC_GATE_GET_INFO_OP` = 0x11 }  
*Operations on the IPC-gate.*
- enum `L4_platform_ctl_ops` {  
`L4_PLATFORM_CTL_SYS_SUSPEND_OP` = 0UL , `L4_PLATFORM_CTL_SYS_SHUTDOWN_OP` = 1UL ,  
`L4_PLATFORM_CTL_CPU_ALLOW_SHUTDOWN_OP` = 2UL , `L4_PLATFORM_CTL_CPU_ENABLE_OP` =  
3UL ,  
`L4_PLATFORM_CTL_CPU_DISABLE_OP` = 4UL , `L4_PLATFORM_CTL_SET_TASK_ASID_OP` = 0x10UL }  
*Operations on platform-control objects.*
- enum `L4_task_ops` {  
`L4_TASK_MAP_OP` = 0UL , `L4_TASK_UNMAP_OP` = 1UL , `L4_TASK_CAP_INFO_OP` = 2UL ,  
`L4_TASK_ADD_KU_MEM_OP` = 3UL ,  
`L4_TASK_LDT_SET_X86_OP` = 0x11UL , `L4_TASK_MAP_VGICC_ARM_OP` = 0x12UL }  
*Operations on task objects.*
- enum `L4_thread_ops` {  
`L4_THREAD_CONTROL_OP` = 0UL , `L4_THREAD_EX_REGS_OP` = 1UL , `L4_THREAD_SWITCH_OP` =  
2UL , `L4_THREAD_STATS_OP` = 3UL ,  
`L4_THREAD_VCPU_RESUME_OP` = 4UL , `L4_THREAD_REGISTER_DELETE_IRQ_OP` = 5UL ,  
`L4_THREAD_MODIFY_SENDER_OP` = 6UL , `L4_THREAD_VCPU_CONTROL_OP` = 7UL ,  
`L4_THREAD_VCPU_CONTROL_EXT_OP` = `L4_THREAD_VCPU_CONTROL_OP` | 0x10000 , `L4_THREAD_REGISTER_DO`  
= 8UL , `L4_THREAD_X86_GDT_OP` = 0x10UL , `L4_THREAD_ARM_TPIDRURO_OP` = 0x10UL ,  
`L4_THREAD_AMD64_SET_SEGMENT_BASE_OP` = 0x12UL , `L4_THREAD_AMD64_GET_SEGMENT_INFO_OP`  
= 0x13UL , `L4_THREAD_OPCODE_MASK` = 0xffff }  
*Operations on thread objects.*
- enum `L4_vcon_ops` { `L4_VCON_WRITE_OP` = 0UL , `L4_VCON_READ_OP` = 1UL , `L4_VCON_SET_ATTR_OP`  
= 2UL , `L4_VCON_GET_ATTR_OP` = 3UL }  
*Operations on vcon objects.*

### 13.6.1 Detailed Description

List of protocol specific opcodes used for communication with [L4Re](#) and Kernel objects.

### 13.6.2 Enumeration Type Documentation

#### 13.6.2.1 L4\_icu\_opcode

```
enum L4_icu_opcode
```

Opcodes to the ICU interface.

#### Enumerator

---

L4_ICU_OP_BIND	Bind opcode.  See also <a href="#">l4_icu_bind()</a>
L4_ICU_OP_UNBIND	Unbind opcode.  See also <a href="#">l4_icu_unbind()</a>
L4_ICU_OP_INFO	Info opcode.  See also <a href="#">l4_icu_info()</a>
L4_ICU_OP_MSI_INFO	Msi-info opcode.  See also <a href="#">l4_icu_msi_info()</a>
L4_ICU_OP_UNMASK	Unmask opcode.  See also <a href="#">l4_icu_unmask()</a>
L4_ICU_OP_MASK	Mask opcode.  See also <a href="#">l4_icu_mask()</a>
L4_ICU_OP_SET_MODE	Set-mode opcode.  See also <a href="#">l4_icu_set_mode()</a>

Definition at line 97 of file [icu.h](#).

### 13.6.2.2 L4\_ipc\_gate\_ops

enum [L4\\_ipc\\_gate\\_ops](#)

Operations on the IPC-gate.

#### Enumerator

L4_IPC_GATE_BIND_OP	Bind operation.
L4_IPC_GATE_GET_INFO_OP	Info operation.

Definition at line 108 of file [ipc\\_gate.h](#).

### 13.6.2.3 L4\_platform\_ctl\_ops

enum [L4\\_platform\\_ctl\\_ops](#)

Operations on platform-control objects.

See [L4\\_PROTO\\_PLATFORM\\_CTL](#) for the protocol type to use for messages to platform-control objects.

#### Enumerator

L4_PLATFORM_CTL_SYS_SUSPEND_OP	Suspend.
L4_PLATFORM_CTL_SYS_SHUTDOWN_OP	shutdown/reboot
L4_PLATFORM_CTL_CPU_ALLOW_SHUTDOWN_OP	allow CPU shutdown
L4_PLATFORM_CTL_CPU_ENABLE_OP	enable an offline CPU
L4_PLATFORM_CTL_CPU_DISABLE_OP	disable an online CPU
L4_PLATFORM_CTL_SET_TASK_ASID_OP	Arm: set task ASID.

Definition at line 159 of file [platform\\_control.h](#).

### 13.6.2.4 L4\_task\_ops

enum [L4\\_task\\_ops](#)

Operations on task objects.

#### Enumerator

L4_TASK_MAP_OP	Map.
L4_TASK_UNMAP_OP	Unmap.
L4_TASK_CAP_INFO_OP	Cap info.
L4_TASK_ADD_KU_MEM_OP	Add kernel-user memory.
L4_TASK_LDT_SET_X86_OP	x86: LDT set
L4_TASK_MAP_VGICC_ARM_OP	Arm: Map virtual GICC area.

Definition at line 341 of file [task.h](#).

### 13.6.2.5 L4\_thread\_ops

enum [L4\\_thread\\_ops](#)

Operations on thread objects.

#### Enumerator

L4_THREAD_CONTROL_OP	Control operation.
----------------------	--------------------

L4_THREAD_EX_REGS_OP	Exchange registers operation.
L4_THREAD_SWITCH_OP	Do a thread switch.
L4_THREAD_STATS_OP	Thread statistics.
L4_THREAD_VCPU_RESUME_OP	VCPU resume.
L4_THREAD_REGISTER_DELETE_IRQ_OP	Register an IPC-gate deletion IRQ.
L4_THREAD_MODIFY_SENDER_OP	Modify all senders IDs that match the given pattern.
L4_THREAD_VCPU_CONTROL_OP	Enable / disable VCPU feature.
L4_THREAD_REGISTER_DOORBELL_IRQ_OP	Register direct IRQ injection doorbell IRQ.
L4_THREAD_X86_GDT_OP	Gdt.
L4_THREAD_ARM_TPIDRURO_OP	Set TPIDRURO register.
L4_THREAD_AMD64_SET_SEGMENT_BASE_OP	Set segment base.
L4_THREAD_AMD64_GET_SEGMENT_INFO_OP	Get segment information.
L4_THREAD_OPCODE_MASK	Mask for opcodes.

Definition at line 732 of file [thread.h](#).

### 13.6.2.6 L4\_vcon\_ops

enum [L4\\_vcon\\_ops](#)

Operations on vcon objects.

#### Enumerator


L4_VCON_WRITE_OP	Write.
L4_VCON_READ_OP	Read.
L4_VCON_SET_ATTR_OP	Get console attributes.
L4_VCON_GET_ATTR_OP	Set console attributes.

Definition at line 291 of file [vcon.h](#).



## 13.7 L4 VIRTIO Interface

Collaboration diagram for L4 VIRTIO Interface:



### Topics


- L4 VIRTIO Transport Layer . . . . . 475  
[L4 specific VIRTIO Transport layer.](#)
- L4 VIRTIO Block Device . . . . . 484
- L4 VIRTIO Input Device . . . . . 486
- L4 VIRTIO Network Device . . . . . 486

### 13.7.1 Detailed Description

#### 13.7.2 L4 VIRTIO Transport Layer

[L4 specific VIRTIO Transport layer.](#)

Collaboration diagram for L4 VIRTIO Transport Layer:



## Namespaces

- namespace [L4virtio](#)  
*L4-VIRTIO Transport C++ API.*

## Data Structures

- struct [l4virtio\\_config\\_hdr\\_t](#)  
*L4-VIRTIO config header, provided in shared data space.*
- struct [l4virtio\\_config\\_queue\\_t](#)  
*Queue configuration entry.*

## Typedefs

- typedef struct l4virtio\_config\_hdr\_t [l4virtio\\_config\\_hdr\\_t](#)  
*L4-VIRTIO config header, provided in shared data space.*
- typedef struct l4virtio\_config\_queue\_t [l4virtio\\_config\\_queue\\_t](#)  
*Queue configuration entry.*

## Enumerations

- enum [L4\\_virtio\\_protocol](#)  
*L4-VIRTIO protocol number.*
- enum [L4\\_virtio\\_opcodes](#) {  
[L4VIRTIO\\_OP\\_SET\\_STATUS](#) = 0 , [L4VIRTIO\\_OP\\_CONFIG\\_QUEUE](#) = 1 , [L4VIRTIO\\_OP\\_REGISTER\\_DS](#) = 3 , [L4VIRTIO\\_OP\\_DEVICE\\_CONFIG](#) = 4 ,  
[L4VIRTIO\\_OP\\_GET\\_DEVICE\\_IRQ](#) = 5 }  
*Opcodes to setup and configure a device.*
- enum [L4virtio\\_device\\_ids](#) {  
[L4VIRTIO\\_ID\\_NET](#) = 1 , [L4VIRTIO\\_ID\\_BLOCK](#) = 2 , [L4VIRTIO\\_ID\\_CONSOLE](#) = 3 , [L4VIRTIO\\_ID\\_RNG](#) = 4 ,  
[L4VIRTIO\\_ID\\_BALLOON](#) = 5 , [L4VIRTIO\\_ID\\_RPMMSG](#) = 7 , [L4VIRTIO\\_ID\\_SCSI](#) = 8 , [L4VIRTIO\\_ID\\_9P](#) = 9 ,  
[L4VIRTIO\\_ID\\_RPROC\\_SERIAL](#) = 11 , [L4VIRTIO\\_ID\\_CAIF](#) = 12 , [L4VIRTIO\\_ID\\_GPU](#) = 16 , [L4VIRTIO\\_ID\\_INPUT](#) = 18 ,  
[L4VIRTIO\\_ID\\_VSOCK](#) = 19 , [L4VIRTIO\\_ID\\_CRYPTIO](#) = 20 , [L4VIRTIO\\_ID\\_FS](#) = 26 , [L4VIRTIO\\_ID\\_SCMI](#) = 32 ,  
[L4VIRTIO\\_ID\\_I2C](#) = 34 , [L4VIRTIO\\_ID\\_WATCHDOG](#) = 35 , [L4VIRTIO\\_ID\\_CAN](#) = 36 , [L4VIRTIO\\_ID\\_GPIO](#) = 41 ,  
[L4VIRTIO\\_ID\\_SPI](#) = 45 , [L4VIRTIO\\_ID\\_SOCKET](#) = 0x9999 }  
*Virtio device IDs as reported in the driver's config space.*
- enum [L4virtio\\_device\\_status](#) {  
[L4VIRTIO\\_STATUS\\_ACKNOWLEDGE](#) = 1 , [L4VIRTIO\\_STATUS\\_DRIVER](#) = 2 , [L4VIRTIO\\_STATUS\\_DRIVER\\_OK](#) = 4 , [L4VIRTIO\\_STATUS\\_FEATURES\\_OK](#) = 8 ,  
[L4VIRTIO\\_STATUS\\_DEVICE\\_NEEDS\\_RESET](#) = 0x40 , [L4VIRTIO\\_STATUS\\_FAILED](#) = 0x80 }  
*Virtio device status bits.*
- enum [L4virtio\\_feature\\_bits](#) { [L4VIRTIO\\_FEATURE\\_VERSION\\_1](#) = 32 , [L4VIRTIO\\_FEATURE\\_CMD\\_CONFIG](#) = 160 }  
*L4virtio-specific feature bits.*
- enum [L4\\_virtio\\_irq\\_status](#) { [L4VIRTIO\\_IRQ\\_STATUS\\_VRING](#) = 1 , [L4VIRTIO\\_IRQ\\_STATUS\\_CONFIG](#) = 2 }  
*VIRTIO IRQ status codes (l4virtio\_config\_hdr\_t::irq\_status).*
- enum [L4\\_virtio\\_cmd](#) {  
[L4VIRTIO\\_CMD\\_NONE](#) = 0x00000000 , [L4VIRTIO\\_CMD\\_SET\\_STATUS](#) = 0x01000000 , [L4VIRTIO\\_CMD\\_CFG\\_QUEUE](#) = 0x02000000 , [L4VIRTIO\\_CMD\\_CFG\\_CHANGED](#) = 0x04000000 ,  
[L4VIRTIO\\_CMD\\_NOTIFY\\_QUEUE](#) = 0x08000000 , [L4VIRTIO\\_CMD\\_MASK](#) = 0xff000000 }  
*Virtio commands for device configuration.*

## Functions

- [L4\\_BEGIN\\_DECLS](#) [l4virtio\\_config\\_queue\\_t](#) \* [l4virtio\\_config\\_queues](#) ([l4virtio\\_config\\_hdr\\_t](#) const \*cfg)  
*Get the pointer to the first queue config.*
- void \* [l4virtio\\_device\\_config](#) ([l4virtio\\_config\\_hdr\\_t](#) const \*cfg)  
*Get the pointer to the device configuration.*
- void [l4virtio\\_set\\_feature](#) ([l4\\_uint32\\_t](#) \*feature\_map, unsigned feat)  
*Set the given feature bit in a feature map.*
- void [l4virtio\\_clear\\_feature](#) ([l4\\_uint32\\_t](#) \*feature\_map, unsigned feat)  
*Clear the given feature bit in a feature map.*
- unsigned [l4virtio\\_get\\_feature](#) ([l4\\_uint32\\_t](#) \*feature\_map, unsigned feat)  
*Check if the given bit in a feature map is set.*
- int [l4virtio\\_set\\_status](#) ([l4\\_cap\\_idx\\_t](#) cap, unsigned status) [L4\\_NOTHROW](#)
- int [l4virtio\\_config\\_queue](#) ([l4\\_cap\\_idx\\_t](#) cap, unsigned queue) [L4\\_NOTHROW](#)
- int [l4virtio\\_register\\_ds](#) ([l4\\_cap\\_idx\\_t](#) cap, [l4\\_cap\\_idx\\_t](#) ds\_cap, [l4\\_uint64\\_t](#) base, [l4\\_umword\\_t](#) offset, [l4\\_umword\\_t](#) size) [L4\\_NOTHROW](#)
- int [l4virtio\\_device\\_config\\_ds](#) ([l4\\_cap\\_idx\\_t](#) cap, [l4\\_cap\\_idx\\_t](#) config\_ds, [l4\\_addr\\_t](#) \*ds\_offset) [L4\\_NOTHROW](#)
- int [l4virtio\\_device\\_notification\\_irq](#) ([l4\\_cap\\_idx\\_t](#) cap, unsigned index, [l4\\_cap\\_idx\\_t](#) irq) [L4\\_NOTHROW](#)

### 13.7.2.1 Detailed Description

[L4](#) specific VIRTIO Transport layer.

The [L4](#) specific VIRTIO Transport layer is based on [L4Re::Dataspace](#) as shared memory and [L4::Irq](#) for signaling. The VIRTIO configuration space is mostly based on a shared memory implementation too and accompanied by two IPC functions to synchronize the configuration between device and driver.

### 13.7.2.2 Typedef Documentation

#### 13.7.2.2.1 [l4virtio\\_config\\_queue\\_t](#)

```
typedef struct l4virtio_config_queue_t l4virtio_config_queue_t
```

Queue configuration entry.

An array of such entries is available at the [l4virtio\\_config\\_hdr\\_t::queues\\_offset](#) in the config data space.

Consistency rules for the queue config are:

- A driver might read `num_max` at any time.
- A driver must write to `num`, `desc_addr`, `avail_addr`, and `used_addr` only when `ready` is zero (0). Values in these fields are validated and used by the device only after successfully setting `ready` to one (1), either by the IPC or by `L4VIRTIO_CMD_CFG_QUEUE`.
- The value of `device_notify_index` is valid only when `ready` is one.
- The driver might write to `device_notify_index` at any time, however the change is guaranteed to take effect after a successful `L4VIRTIO_CMD_CFG_QUEUE` or after a `config_queue` IPC. Note, the change might also have immediate effect, depending on the device implementation.

### 13.7.2.3 Enumeration Type Documentation

#### 13.7.2.3.1 L4\_virtio\_cmd

enum [L4\\_virtio\\_cmd](#)

Virtio commands for device configuration.

##### Enumerator

L4VIRTIO_CMD_NONE	No command pending.
L4VIRTIO_CMD_SET_STATUS	Set the status register.
L4VIRTIO_CMD_CFG_QUEUE	Configure a queue.
L4VIRTIO_CMD_CFG_CHANGED	Device config changed.
L4VIRTIO_CMD_NOTIFY_QUEUE	Configure a queue.
L4VIRTIO_CMD_MASK	Mask to get command bits.

Definition at line 122 of file [virtio.h](#).

#### 13.7.2.3.2 L4\_virtio\_irq\_status

enum [L4\\_virtio\\_irq\\_status](#)

VIRTIO IRQ status codes ([l4virtio\\_config\\_hdr\\_t::irq\\_status](#)).

##### Note

[l4virtio\\_config\\_hdr\\_t::irq\\_status](#) is currently unused.

##### Enumerator

L4VIRTIO_IRQ_STATUS_VRING	VRING IRQ pending flag.
L4VIRTIO_IRQ_STATUS_CONFIG	CONFIG IRQ pending flag.

Definition at line 113 of file [virtio.h](#).

#### 13.7.2.3.3 L4\_virtio\_opcodes

enum [L4\\_virtio\\_opcodes](#)

Opcodes to setup and configure a device.

##### Enumerator

L4VIRTIO_OP_SET_STATUS	Write device status register.
------------------------	-------------------------------

L4VIRTIO_OP_CONFIG_QUEUE	Configure queue.
L4VIRTIO_OP_REGISTER_DS	Register shared memory with device.
L4VIRTIO_OP_DEVICE_CONFIG	Get device config page.
L4VIRTIO_OP_GET_DEVICE_IRQ	Retrieve device notification IRQ.

Definition at line 52 of file [virtio.h](#).

#### 13.7.2.3.4 L4virtio\_device\_ids

enum [L4virtio\\_device\\_ids](#)

Virtio device IDs as reported in the driver's config space.

##### Enumerator

L4VIRTIO_ID_NET	Virtual ethernet card.
L4VIRTIO_ID_BLOCK	General block device.
L4VIRTIO_ID_CONSOLE	Simple device for data IO via ports.
L4VIRTIO_ID_RNG	Entropy source.
L4VIRTIO_ID_BALLOON	Memory ballooning device.
L4VIRTIO_ID_RPMMSG	Device using rpmsg protocol.
L4VIRTIO_ID_SCSI	SCSI host device.
L4VIRTIO_ID_9P	Device using 9P transport protocol.
L4VIRTIO_ID_RPROC_SERIAL	Rproc serial device.
L4VIRTIO_ID_CAIF	Device using CAIF network protocol.
L4VIRTIO_ID_GPU	GPU.
L4VIRTIO_ID_INPUT	Input.
L4VIRTIO_ID_VSOCK	Vsock transport.
L4VIRTIO_ID_CRYPT	Crypto.
L4VIRTIO_ID_FS	FS.
L4VIRTIO_ID_SCM	Scmi device.
L4VIRTIO_ID_I2C	I2C device.
L4VIRTIO_ID_WATCHDOG	Watchdog device.
L4VIRTIO_ID_CAN	CAN device.
L4VIRTIO_ID_GPIO	Gpio device.
L4VIRTIO_ID_SPI	SPI device.
L4VIRTIO_ID_SOCKET	Unofficial socket device.

Definition at line 62 of file [virtio.h](#).

### 13.7.2.3.5 L4virtio\_device\_status

enum [L4virtio\\_device\\_status](#)

Virtio device status bits.

#### Enumerator

L4VIRTIO_STATUS_ACKNOWLEDGE	Guest OS has found device.
L4VIRTIO_STATUS_DRIVER	Guest OS knows how to drive device.
L4VIRTIO_STATUS_DRIVER_OK	Driver is set up.
L4VIRTIO_STATUS_FEATURES_OK	Driver has acknowledged feature set.
L4VIRTIO_STATUS_DEVICE_NEEDS_RESET	Device detected fatal error.
L4VIRTIO_STATUS_FAILED	Driver detected fatal error.

Definition at line 90 of file [virtio.h](#).

### 13.7.2.3.6 L4virtio\_feature\_bits

enum [L4virtio\\_feature\\_bits](#)

L4virtio-specific feature bits.

#### Enumerator

L4VIRTIO_FEATURE_VERSION_1	Virtio protocol version 1 supported. Must be 1 for <a href="#">L4virtio</a> .
L4VIRTIO_FEATURE_CMD_CONFIG	Status and queue config are set via cmd field instead of via IPC.

Definition at line 101 of file [virtio.h](#).

## 13.7.2.4 Function Documentation

### 13.7.2.4.1 l4virtio\_config\_queue()

```
int l4virtio_config_queue (
    l4\_cap\_idx\_t cap,
    unsigned queue)
```

#### Parameters

<i>cap</i>	Capability to the VIRTIO host.
------------	--------------------------------

Trigger queue configuration of the given queue.

Usually all queues are configured when the status is written to running. However, in some cases queues shall be disabled or enabled dynamically, in this case this function triggers a reconfiguration from the shared memory register of the queue config.

**Parameters**

<i>queue</i>	Queue index for the queue to be configured.
--------------	---

**Return values**

<i>0</i>	on success.
<i>-L4_EIO</i>	The queue's status is invalid.
<i>-L4_ERANGE</i>	The queue index exceeds the number of queues.
<i>-L4_EINVAL</i>	Otherwise.

References [L4\\_CV](#), and [L4\\_NOTHROW](#).

**13.7.2.4.2 l4virtio\_config\_queues()**

```
L4_BEGIN_DECLS l4virtio_config_queue_t * l4virtio_config_queues (
    l4virtio_config_hdr_t const * cfg) [inline]
```

Get the pointer to the first queue config.

**Parameters**

<i>cfg</i>	Pointer to the config header.
------------	-------------------------------

**Returns**

pointer to queue config of queue 0.

Definition at line 255 of file [virtio.h](#).

References [l4virtio\\_config\\_hdr\\_t::queues\\_offset](#).

**13.7.2.4.3 l4virtio\_device\_config()**

```
void * l4virtio_device_config (
    l4virtio_config_hdr_t const * cfg) [inline]
```

Get the pointer to the device configuration.

**Parameters**

<i>cfg</i>	Pointer to the config header.
------------	-------------------------------

**Returns**

pointer to device configuration structure.

Definition at line 266 of file [virtio.h](#).

#### 13.7.2.4.4 l4virtio\_device\_config\_ds()

```
int l4virtio_device_config_ds (
    l4_cap_idx_t cap,
    l4_cap_idx_t config_ds,
    l4_addr_t * ds_offset)
```

##### Parameters

<i>cap</i>	Capability to the L4-VIRTIO host
------------	----------------------------------

Get the dataspace with the [L4virtio](#) configuration page.

##### Parameters

<i>config_ds</i>	Capability for receiving the dataspace capability for the shared L4-VIRTIO config data space.
<i>ds_offset</i>	Offset into the dataspace where the device configuration structure starts.

References [L4\\_CV](#), and [L4\\_NOTHROW](#).

#### 13.7.2.4.5 l4virtio\_device\_notification\_irq()

```
int l4virtio_device_notification_irq (
    l4_cap_idx_t cap,
    unsigned index,
    l4_cap_idx_t irq)
```

##### Parameters

<i>cap</i>	Capability to the L4-VIRTIO host
------------	----------------------------------

Get the notification interrupt corresponding to the given index.

##### Parameters

	<i>index</i>	Index of the interrupt.
out	<i>irq</i>	Triggerable for the given index.

##### Return values

<i>L4_EOK</i>	Success.
<i>L4_ENOSYS</i>	IRQ notification not supported by device.
<i>&lt;0</i>	Other error.

An index is only guaranteed to return an IRQ object when the index is set in one of the device notify index fields. The device must return the same interrupt for a given index as long as the index is in use. If an index disappears as a result of a configuration change and then is reused later, the interrupt is not guaranteed to be the same.

Interrupts must always be rerequested after a device reset.

References [L4\\_END\\_DECLS](#), and [L4\\_NOTHROW](#).



## 13.7.2.4.6 l4virtio\_register\_ds()

```
int l4virtio_register_ds (
    l4_cap_idx_t cap,
    l4_cap_idx_t ds_cap,
    l4_uint64_t base,
    l4_umword_t offset,
    l4_umword_t size)
```

## Parameters

<i>cap</i>	Capability to the VIRTIO host
------------	-------------------------------

Register a shared data space with VIRTIO host.

## Parameters

<i>ds_cap</i>	Dataspace capability to register. The lower 8 bits determine the rights mask with which the guest's rights are masked during the registration of the dataspace at the VIRTIO host.
<i>base</i>	VIRTIO guest physical start address of shared memory region
<i>offset</i>	Offset within the data space that is attached to the given <i>base</i> in the guest physical memory.
<i>size</i>	Size of the memory region in the guest

## Return values

<i>L4_EOK</i>	Operation successful.
<i>-L4_EINVAL</i>	The <i>ds_cap</i> capability is invalid, does not refer to a valid dataspace, is not a trusted dataspace if trusted dataspace validation is enabled, or <i>size</i> and <i>offset</i> specify an invalid region.
<i>-L4_ENOMEM</i>	The limit of dataspaces that can be registered has been reached or no capability slot could be allocated.
<i>-L4_ERANGE</i>	<i>offset</i> is larger than the size of the dataspace.
<i>&lt; 0</i>	Any error returned by the dataspace when queried for information during setup or any error returned by the region manager from attaching the dataspace.

References [L4\\_CV](#), and [L4\\_NOTHROW](#).

## 13.7.2.4.7 l4virtio\_set\_status()

```
int l4virtio_set_status (
    l4_cap_idx_t cap,
    unsigned status)
```

## Parameters

<i>cap</i>	Capability to the VIRTIO host
------------	-------------------------------

Write the VIRTIO status register.

#### Parameters

<i>status</i>	Status word to write to the VIRTIO status.
---------------	--

#### Return values

0	on success.
---	-------------

#### Note

All other registers are accessed via shared memory.

References [L4\\_CV](#), and [L4\\_NOTHROW](#).

### 13.7.3 L4 VIRTIO Block Device

Collaboration diagram for L4 VIRTIO Block Device:



#### Data Structures

- struct [l4virtio\\_block\\_header\\_t](#)  
*Header structure of a request for a block device.*
- struct [l4virtio\\_block\\_discard\\_t](#)  
*Structure used for the write zeroes and discard commands.*
- struct [l4virtio\\_block\\_config\\_t](#)  
*Device configuration for block devices.*

#### Typedefs

- typedef struct [l4virtio\\_block\\_header\\_t](#) **[l4virtio\\_block\\_header\\_t](#)**  
*Header structure of a request for a block device.*
- typedef struct [l4virtio\\_block\\_discard\\_t](#) **[l4virtio\\_block\\_discard\\_t](#)**  
*Structure used for the write zeroes and discard commands.*
- typedef struct [l4virtio\\_block\\_config\\_t](#) **[l4virtio\\_block\\_config\\_t](#)**  
*Device configuration for block devices.*

## Enumerations

- enum `L4virtio_block_operations` {  
`L4VIRTIO_BLOCK_T_IN` = 0 , `L4VIRTIO_BLOCK_T_OUT` = 1 , `L4VIRTIO_BLOCK_T_FLUSH` = 4 ,  
`L4VIRTIO_BLOCK_T_GET_ID` = 8 ,  
`L4VIRTIO_BLOCK_T_DISCARD` = 11 , `L4VIRTIO_BLOCK_T_WRITE_ZEROES` = 13 }  
*Kinds of operation over a block device.*
- enum `L4virtio_block_status` { `L4VIRTIO_BLOCK_S_OK` = 0 , `L4VIRTIO_BLOCK_S_IOERR` = 1 ,  
`L4VIRTIO_BLOCK_S_UNSUPP` = 2 }  
*Status of a finished block request.*
- enum `L4virtio_block_feature_bits`  
*Block device feature bits.*

### 13.7.3.1 Detailed Description

### 13.7.3.2 Enumeration Type Documentation

#### 13.7.3.2.1 L4virtio\_block\_operations

enum `L4virtio_block_operations`

Kinds of operation over a block device.

#### Enumerator

<code>L4VIRTIO_BLOCK_T_IN</code>	Read from device.
<code>L4VIRTIO_BLOCK_T_OUT</code>	Write to device.
<code>L4VIRTIO_BLOCK_T_FLUSH</code>	Flush data to disk.
<code>L4VIRTIO_BLOCK_T_GET_ID</code>	Get device ID.
<code>L4VIRTIO_BLOCK_T_DISCARD</code>	Discard a range of sectors.
<code>L4VIRTIO_BLOCK_T_WRITE_ZEROES</code>	Write zeroes to a range of sectors.

Definition at line 19 of file `virtio_block.h`.

#### 13.7.3.2.2 L4virtio\_block\_status

enum `L4virtio_block_status`

Status of a finished block request.


#### Enumerator

<code>L4VIRTIO_BLOCK_S_OK</code>	Request finished successfully.
<code>L4VIRTIO_BLOCK_S_IOERR</code>	IO error on device.
<code>L4VIRTIO_BLOCK_S_UNSUPP</code>	Operation is not supported.

Definition at line 32 of file `virtio_block.h`.

### 13.7.4 L4 VIRTIO Input Device

Collaboration diagram for L4 VIRTIO Input Device:



#### Data Structures

- struct [l4virtio\\_input\\_absinfo\\_t](#)  
*Information about the absolute axis in the underlying evdev implementation.*
- struct [l4virtio\\_input\\_devids\\_t](#)  
*Device ID information for the device.*
- struct [l4virtio\\_input\\_config\\_t](#)  
*Device configuration for input devices.*
- struct [l4virtio\\_input\\_event\\_t](#)  
*Single event in event or status queue.*

#### Typedefs

- typedef struct [l4virtio\\_input\\_absinfo\\_t](#) [l4virtio\\_absinfo\\_t](#)  
*Information about the absolute axis in the underlying evdev implementation.*
- typedef struct [l4virtio\\_input\\_devids\\_t](#) [l4virtio\\_input\\_devids\\_t](#)  
*Device ID information for the device.*
- typedef struct [l4virtio\\_input\\_config\\_t](#) [l4virtio\\_input\\_config\\_t](#)  
*Device configuration for input devices.*
- typedef struct [l4virtio\\_input\\_event\\_t](#) [l4virtio\\_input\\_event\\_t](#)  
*Single event in event or status queue.*

#### Enumerations

- enum [L4virtio\\_input\\_config\\_select](#)  
*Device information selectors.*

#### 13.7.4.1 Detailed Description

### 13.7.5 L4 VIRTIO Network Device

Collaboration diagram for L4 VIRTIO Network Device:



## Data Structures

- struct [l4virtio\\_net\\_header\\_t](#)  
*Header structure of a request for a network device.*
- struct [l4virtio\\_net\\_config\\_t](#)  
*Device configuration for network devices.*

## Typedefs

- typedef struct l4virtio\_net\_header\_t **l4virtio\_net\_header\_t**  
*Header structure of a request for a network device.*
- typedef struct l4virtio\_net\_config\_t **l4virtio\_net\_config\_t**  
*Device configuration for network devices.*

## Enumerations


- enum [L4virtio\\_net\\_feature\\_bits](#)  
*Network device feature bits.*

### 13.7.5.1 Detailed Description

## 13.8 L4 Vbus functions

C interface of the Vbus API.

Collaboration diagram for L4 Vbus functions:



## Topics

- [L4vbus GPIO functions](#) . . . . . [497](#)
- [L4vbus PCI functions](#) . . . . . [508](#)
- [L4vbus power management functions](#) . . . . . [514](#)

## Enumerations

- enum `L4vbus_dma_domain_assign_flags` { `L4VBUS_DMAD_UNBIND` = 0 , `L4VBUS_DMAD_BIND` = 1 , `L4VBUS_DMAD_L4RE_DMA_SPACE` = 0 , `L4VBUS_DMAD_KERNEL_DMA_SPACE` = 2 }

*Flags for `l4vbus_assign_dma_domain()`.*

## Functions

- `L4_BEGIN_DECLS` int `l4vbus_get_device_by_hid` (`l4_cap_idx_t` vbus, `l4vbus_device_handle_t` parent, `l4vbus_device_handle_t` \*child, char const \*hid, int depth, `l4vbus_device_t` \*devinfo)  
*Find a device by the hardware interface identifier (HID).*
- int `l4vbus_get_next_device` (`l4_cap_idx_t` vbus, `l4vbus_device_handle_t` parent, `l4vbus_device_handle_t` \*child, int depth, `l4vbus_device_t` \*devinfo)  
*Find next child following `child`.*
- int `l4vbus_get_device` (`l4_cap_idx_t` vbus, `l4vbus_device_handle_t` dev, `l4vbus_device_t` \*devinfo)  
*Obtain detailed information about a Vbus device.*
- int `l4vbus_get_resource` (`l4_cap_idx_t` vbus, `l4vbus_device_handle_t` dev, unsigned res\_idx, `l4vbus_resource_t` \*res)  
*Obtain the resource description of an individual device resource.*
- int `l4vbus_is_compatible` (`l4_cap_idx_t` vbus, `l4vbus_device_handle_t` dev, char const \*cid)  
*Check if the given device has a compatibility ID (CID) or HID that matches `cid`.*
- int `l4vbus_get_hid` (`l4_cap_idx_t` vbus, `l4vbus_device_handle_t` dev, char \*hid, unsigned long max\_len)  
*Get the HID (hardware identifier) of a device.*
- int `l4vbus_get_adr` (`l4_cap_idx_t` vbus, `l4vbus_device_handle_t` dev, `l4_uint32_t` \*adr)  
*Get the bus-specific address of a device.*
- int `l4vbus_request_ioport` (`l4_cap_idx_t` vbus, `l4vbus_resource_t` const \*res)  
*Request an IO port resource.*
- int `l4vbus_assign_dma_domain` (`l4_cap_idx_t` vbus, unsigned domain\_id, unsigned flags, `l4_cap_idx_t` dma\_space)  
*Bind or unbind a kernel [DMA space](#) or a `L4Re::Dma_space` to a DMA domain.*
- int `l4vbus_release_ioport` (`l4_cap_idx_t` vbus, `l4vbus_resource_t` const \*res)  
*Release a previously requested IO port resource.*
- int `l4vbus_vicu_get_cap` (`l4_cap_idx_t` vbus, `l4vbus_device_handle_t` icu, `l4_cap_idx_t` cap)  
*Get capability of ICU.*

### 13.8.1 Detailed Description

C interface of the Vbus API.

The virtual bus (Vbus) is a hierarchical (tree) structure of device nodes where each device has a set of resources attached to it. Each virtual bus provides an Icu ([Interrupt controller](#)) for interrupt handling.

The Vbus interface allows a client to find and query devices present on his virtual bus. After obtaining a device handle for a specific device the client can enumerate its resources.

#### Include File

```
#include <l4/vbus/vbus.h>
```

Refer to [L4vbus](#) for the C++ API.

## 13.8.2 Enumeration Type Documentation

### 13.8.2.1 L4vbus\_dma\_domain\_assign\_flags

enum [L4vbus\\_dma\\_domain\\_assign\\_flags](#)

Flags for [l4vbus\\_assign\\_dma\\_domain\(\)](#).

#### Enumerator

L4VBUS_DMAD_UNBIND	Unbind the given DMA space from the DMA domain.
L4VBUS_DMAD_BIND	Bind the given DMA space to the DMA domain.
L4VBUS_DMAD_L4RE_DMA_SPACE	The given DMA space is an <a href="#">L4Re::Dma_space</a> .
L4VBUS_DMAD_KERNEL_DMA_SPACE	The given DMA space is a kernel DMA space ( <a href="#">L4::Task</a> ).

Definition at line [174](#) of file [vbus.h](#).

## 13.8.3 Function Documentation

### 13.8.3.1 l4vbus\_assign\_dma\_domain()

```
int l4vbus_assign_dma_domain (
    l4_cap_idx_t vbus,
    unsigned domain_id,
    unsigned flags,
    l4_cap_idx_t dma_space)
```

Bind or unbind a kernel [DMA space](#) or a [L4Re::Dma\\_space](#) to a DMA domain.

#### Parameters

<i>vbus</i>	Capability of the system bus
<i>domain_id</i>	DMA domain ID (resource address of DMA domain found on the vBUS). If the value is ~0U the DMA space of the whole vBUS is used.
<i>flags</i>	A combination of <a href="#">L4vbus_dma_domain_assign_flags</a> .
<i>dma_space</i>	The DMA space capability to bind or unbind, this must either be an <a href="#">L4Re::Dma_space</a> or a kernel <a href="#">DMA space</a> ( <a href="#">L4::Task</a> created with L4_PROTO_DMA_SPACE) and the type must be reflected in the <i>flags</i> .


#### Return values

<i>0</i>	Operation completed successfully.
<i>-L4_ENOENT</i>	The vbus does not support a global DMA domain or no DMA domain could be found.
<i>-L4_EINVAL</i>	Invalid argument used.
<i>-L4_EBUSY</i>	DMA domain is already active, this means another DMA space is already assigned.

References [L4\\_CV](#).

Referenced by [L4vbus::Vbus::assign\\_dma\\_domain\(\)](#), and [L4vbus::Vbus::assign\\_dma\\_domain\(\)](#).

Here is the caller graph for this function:



### 13.8.3.2 l4vbus\_get\_adr()

```
int l4vbus_get_adr (
    l4_cap_idx_t vbus,
    l4vbus_device_handle_t dev,
    l4_uint32_t * adr)
```

Get the bus-specific address of a device.

#### Parameters

	<i>vbus</i>	Capability of the system bus
	<i>dev</i>	Handle of the device
out	<i>adr</i>	Address

#### Return values

<i>L4_EOK</i>	Success.
<i>-L4_ENOSYS</i>	Device has no valid address.

References [L4\\_CV](#).

### 13.8.3.3 l4vbus\_get\_device()

```
int l4vbus_get_device (
    l4_cap_idx_t vbus,
    l4vbus_device_handle_t dev,
    l4vbus_device_t * devinfo)
```

Obtain detailed information about a Vbus device.



**Parameters**

	<i>vbus</i>	Capability of the vbus to which the device is connected.
	<i>dev</i>	Device handle of the device from which to retrieve the details.
out	<i>devinfo</i>	Information structure which contains details about the device. The pointer might be NULL.

**Return values**

<i>0</i>	Success.
<i>-L4_ENODEV</i>	No device with the given device handle <i>dev</i> could be found.

References [L4\\_CV](#).

Referenced by [L4vbus::Device::device\(\)](#).

Here is the caller graph for this function:

**13.8.3.4 l4vbus\_get\_device\_by\_hid()**

```

L4_BEGIN_DECLS int l4vbus_get_device_by_hid (
    l4_cap_idx_t vbus,
    l4vbus_device_handle_t parent,
    l4vbus_device_handle_t * child,
    char const * hid,
    int depth,
    l4vbus_device_t * devinfo)
  
```

Find a device by the hardware interface identifier (HID).

**Parameters**

<i>vbus</i>	Capability of the system bus
<i>parent</i>	Handle to the parent to start the search

This function searches the vbus for a device with the given HID and returns a handle to the first matching device. The HID usually conforms to an ACPI HID or a Linux device tree compatible identifier.

It is possible to have multiple devices with the same HID on a vbus. In order to find all matching devices this function has to be called repeatedly with *child* pointing to the device found in the previous iteration. The iteration starts at *child* that might be any device node in the tree.

**Parameters**

<i>in, out</i>	<i>child</i>	Handle of the device from where in the device tree the search should start. To start searching from the beginning <i>child</i> must be initialized using the default ( <a href="#">L4VBUS_NULL</a> ). If a matching device is found, its handle is returned through this parameter.
	<i>hid</i>	HID of the device
	<i>depth</i>	Maximum depth for the recursive lookup
<i>out</i>	<i>devinfo</i>	Device information structure (might be NULL)


**Return values**

<i>&gt;=0</i>	A device with the given HID was found.
<i>-L4_ENOENT</i>	No device with the given HID could be found on the vbus.
<i>-L4_EINVAL</i>	Invalid or no HID provided.
<i>-L4_ENODEV</i>	Function called on a non-existing device.

References [L4\\_CV](#).

Referenced by [L4vbus::Device::device\\_by\\_hid\(\)](#).

Here is the caller graph for this function:

**13.8.3.5 l4vbus\_get\_hid()**

```

int l4vbus_get_hid (
    l4_cap_idx_t vbus,
    l4vbus_device_handle_t dev,
    char * hid,
    unsigned long max_len)

```

Get the HID (hardware identifier) of a device.

**Parameters**

<i>vbus</i>	Capability of the system bus
<i>dev</i>	Handle of the device
<i>hid</i>	Pointer to a buffer for the HID string

<i>max_len</i>	The size of the buffer ( <i>hid</i> )
----------------	---------------------------------------

**Returns**

the length of the HID string on success, else failure

References [L4\\_CV](#).

**13.8.3.6 l4vbus\_get\_next\_device()**

```
int l4vbus_get_next_device (
    l4_cap_idx_t vbus,
    l4vbus_device_handle_t parent,
    l4vbus_device_handle_t * child,
    int depth,
    l4vbus_device_t * devinfo)
```

Find next child following *child*.

**Parameters**

	<i>vbus</i>	Capability of the system bus
	<i>parent</i>	Handle to the parent device (use <a href="#">L4VBUS_ROOT_BUS</a> for the system bus)
in, out	<i>child</i>	Handle of the device that precedes the device that shall be returned. To start from the beginning, <i>child</i> must be initialized with <a href="#">L4VBUS_NULL</a> . If a device is found, its handle is returned through this parameter.
	<i>depth</i>	Depth to look for
out	<i>devinfo</i>	Device information (might be NULL)


**Returns**

0 on success, else failure

References [L4\\_CV](#).

Referenced by [L4vbus::Device::next\\_device\(\)](#).

Here is the caller graph for this function:



### 13.8.3.7 l4vbus\_get\_resource()

```
int l4vbus_get_resource (
    l4_cap_idx_t vbus,
    l4vbus_device_handle_t dev,
    unsigned res_idx,
    l4vbus_resource_t * res)
```

Obtain the resource description of an individual device resource.

#### Parameters

	<i>vbus</i>	Capability of the vbus to which the device is connected.
	<i>dev</i>	Device handle of the device on the vbus. The device handle can be obtained by using the <a href="#">l4vbus_get_device_by_hid()</a> and <a href="#">l4vbus_get_next_device()</a> functions.
	<i>res_idx</i>	Index of the resource for which the resource description should be returned. The total number of resources for a device is available in the <a href="#">l4vbus_device_t</a> structure that is returned by <a href="#">L4vbus::Device::device_by_hid()</a> and <a href="#">L4vbus::Device::next_device()</a> .
out	<i>res</i>	Descriptor of the resource.

This function returns the resource descriptor of an individual device resource selected by the *res\_idx* parameter.


#### Return values

0	Success.
-L4_ENOENT	Invalid resource index <i>res_idx</i> .

References [L4\\_CV](#).

Referenced by [L4vbus::Device::get\\_resource\(\)](#).

Here is the caller graph for this function:



### 13.8.3.8 l4vbus\_is\_compatible()

```
int l4vbus_is_compatible (
    l4_cap_idx_t vbus,
    l4vbus_device_handle_t dev,
    char const * cid)
```

Check if the given device has a compatibility ID (CID) or HID that matches *cid*.

#### Parameters

<i>vbus</i>	Capability of the system bus
<i>dev</i>	device handle for which the CID shall be tested
<i>cid</i>	the compatibility ID to test


#### Returns

1 when the given ID (*cid*) matches this device, 0 when the given ID does not match, <0 on error.

References [L4\\_CV](#).

Referenced by [L4vbus::Device::is\\_compatible\(\)](#).

Here is the caller graph for this function:



#### 13.8.3.9 l4vbus\_release\_ioport()

```
int l4vbus_release_ioport (  
    l4_cap_idx_t vbus,  
    l4vbus_resource_t const * res)
```

Release a previously requested IO port resource.

#### Parameters

	<i>vbus</i>	Capability of the system bus.
in	<i>res</i>	The IO port resource to be released from the bus.


**Returns**

$\geq 0$  on success,  $< 0$  on error.

References [L4\\_CV](#).

Referenced by [L4vbus::Vbus::release\\_ioport\(\)](#).

Here is the caller graph for this function:

**13.8.3.10 l4vbus\_request\_ioport()**

```
int l4vbus_request_ioport (
    l4_cap_idx_t vbus,
    l4vbus_resource_t const * res)
```

Request an IO port resource.

**Parameters**

	<i>vbus</i>	Capability of the system bus.
in	<i>res</i>	The IO port resource to be requested from the bus.


**Return values**

0	Success.
-L4_EINVAL	Resource is not an IO port resource.
-L4_ENOENT	No matching IO port resource found.

If any IO port resource is found that contains the requested IO port range the IO ports are obtained.

Referenced by [L4vbus::Vbus::request\\_ioport\(\)](#).

Here is the caller graph for this function:



### 13.8.3.11 l4vbus\_vicu\_get\_cap()

```
int l4vbus_vicu_get_cap (
    l4_cap_idx_t vbus,
    l4vbus_device_handle_t icu,
    l4_cap_idx_t cap)
```

Get capability of ICU.

#### Parameters

<i>vbus</i>	Capability of the system bus.
<i>icu</i>	ICU device handle.
<i>cap</i>	Capability slot for the capability.


#### Returns

0 on success, else failure

References [L4\\_END\\_DECLS](#).

Referenced by [L4vbus::l4vbus\\_vicu\(\)](#).

Here is the caller graph for this function:



## 13.8.4 L4vbus GPIO functions

Collaboration diagram for L4vbus GPIO functions:



## Enumerations

- enum `L4vbus_gpio_generic_func` { `L4VBUS_GPIO_SETUP_INPUT` = 0x100 , `L4VBUS_GPIO_SETUP_OUTPUT` = 0x200 , `L4VBUS_GPIO_SETUP_IRQ` = 0x300 }

*Constants for generic GPIO functions.*

- enum `L4vbus_gpio_pull_modes` { `L4VBUS_GPIO_PIN_PULL_NONE` = 0x100 , `L4VBUS_GPIO_PIN_PULL_UP` = 0x200 , `L4VBUS_GPIO_PIN_PULL_DOWN` = 0x300 }

*Constants for generic GPIO pull up/down resistor configuration.*

## Functions

- int `l4vbus_gpio_setup` (`l4_cap_idx_t` vbus, `l4vbus_device_handle_t` handle, unsigned pin, unsigned mode, int value)

*Configure the function of a GPIO pin.*

- int `l4vbus_gpio_config_pull` (`l4_cap_idx_t` vbus, `l4vbus_device_handle_t` handle, unsigned pin, unsigned mode)

*Generic function to set pull up/down mode.*

- int `l4vbus_gpio_config_pad` (`l4_cap_idx_t` vbus, `l4vbus_device_handle_t` handle, unsigned pin, unsigned func, unsigned value)

*Hardware specific configuration function.*

- int `l4vbus_gpio_config_get` (`l4_cap_idx_t` vbus, `l4vbus_device_handle_t` handle, unsigned pin, unsigned func, unsigned \*value)

*Read hardware specific configuration.*

- int `l4vbus_gpio_get` (`l4_cap_idx_t` vbus, `l4vbus_device_handle_t` handle, unsigned pin)

*Read value of GPIO input pin.*

- int `l4vbus_gpio_set` (`l4_cap_idx_t` vbus, `l4vbus_device_handle_t` handle, unsigned pin, int value)

*Set GPIO output pin.*

- int `l4vbus_gpio_multi_setup` (`l4_cap_idx_t` vbus, `l4vbus_device_handle_t` handle, unsigned offset, unsigned mask, unsigned mode, unsigned value)

*Configure function of multiple GPIO pins at once.*

- int `l4vbus_gpio_multi_config_pad` (`l4_cap_idx_t` vbus, `l4vbus_device_handle_t` handle, unsigned offset, unsigned mask, unsigned func, unsigned value)

*Hardware specific configuration function for multiple GPIO pins.*

- int `l4vbus_gpio_multi_get` (`l4_cap_idx_t` vbus, `l4vbus_device_handle_t` handle, unsigned offset, unsigned \*data)

*Read values of multiple GPIO pins at once.*

- int `l4vbus_gpio_multi_set` (`l4_cap_idx_t` vbus, `l4vbus_device_handle_t` handle, unsigned offset, unsigned mask, unsigned data)

*Set multiple GPIO output pins at once.*

- int `l4vbus_gpio_to_irq` (`l4_cap_idx_t` vbus, `l4vbus_device_handle_t` handle, unsigned pin)

*Create IRQ for GPIO pin.*

### 13.8.4.1 Detailed Description

### 13.8.4.2 Enumeration Type Documentation

#### 13.8.4.2.1 L4vbus\_gpio\_generic\_func

enum `L4vbus_gpio_generic_func`



Constants for generic GPIO functions.

#### Enumerator

L4VBUS_GPIO_SETUP_INPUT	Set GPIO pin to input.
L4VBUS_GPIO_SETUP_OUTPUT	Set GPIO pin to output.
L4VBUS_GPIO_SETUP_IRQ	Set GPIO pin to IRQ.

Definition at line 24 of file [vbus\\_gpio.h](#).

#### 13.8.4.2.2 L4vbus\_gpio\_pull\_modes

```
enum L4vbus_gpio_pull_modes
```

Constants for generic GPIO pull up/down resistor configuration.

#### Enumerator

L4VBUS_GPIO_PIN_PULL_NONE	No pull up or pull down resistors.
L4VBUS_GPIO_PIN_PULL_UP	enable pull up resistor
L4VBUS_GPIO_PIN_PULL_DOWN	enable pull down resistor

Definition at line 34 of file [vbus\\_gpio.h](#).

#### 13.8.4.3 Function Documentation

##### 13.8.4.3.1 l4vbus\_gpio\_config\_get()

```
int l4vbus_gpio_config_get (  
    l4_cap_idx_t vbus,  
    l4vbus_device_handle_t handle,  
    unsigned pin,  
    unsigned func,  
    unsigned * value)
```

Read hardware specific configuration.

#### Parameters

	<i>vbus</i>	V-BUS capability
	<i>handle</i>	Device handle for the GPIO chip
	<i>pin</i>	GPIO pin number
	<i>func</i>	Hardware specific configuration register to read from. Usually this is an offset to the GPIO chip's base address.
out	<i>value</i>	The configuration value.

**Returns**

0 if OK, error code otherwise

References [L4\\_CV](#).

Referenced by [L4vbus::Gpio\\_pin::config\\_get\(\)](#).

Here is the caller graph for this function:

**13.8.4.3.2 l4vbus\_gpio\_config\_pad()**

```

int l4vbus_gpio_config_pad (
    l4_cap_idx_t vbus,
    l4vbus_device_handle_t handle,
    unsigned pin,
    unsigned func,
    unsigned value)
  
```

Hardware specific configuration function.

**Parameters**

<i>vbus</i>	V-BUS capability
<i>handle</i>	Device handle for the GPIO chip
<i>pin</i>	GPIO pin number
<i>func</i>	Hardware specific configuration register, usually offset to the GPIO chip's base address
<i>value</i>	Value which is written into the hardware specific configuration register for the specified pin

**Returns**

0 if OK, error code otherwise

References [L4\\_CV](#).

Referenced by [L4vbus::Gpio\\_pin::config\\_pad\(\)](#).

Here is the caller graph for this function:



#### 13.8.4.3.3 l4vbus\_gpio\_config\_pull()

```
int l4vbus_gpio_config_pull (  
    l4_cap_idx_t vbus,  
    l4vbus_device_handle_t handle,  
    unsigned pin,  
    unsigned mode)
```

Generic function to set pull up/down mode.

##### Parameters

<i>vbus</i>	V-BUS capability
<i>handle</i>	Device handle for the GPIO chip
<i>pin</i>	GPIO pin number
<i>mode</i>	mode for pull up/down resistors, see <a href="#">L4vbus_gpio_pull_modes</a>


##### Returns

0 if OK, error code otherwise

References [L4\\_CV](#).

Referenced by [L4vbus::Gpio\\_pin::config\\_pull\(\)](#).

Here is the caller graph for this function:



#### 13.8.4.3.4 l4vbus\_gpio\_get()

```
int l4vbus_gpio_get (  
    l4_cap_idx_t vbus,  
    l4vbus_device_handle_t handle,  
    unsigned pin)
```

Read value of GPIO input pin.

##### Parameters

<i>vbus</i>	V-BUS capability
-------------	------------------

<i>handle</i>	Device handle for the GPIO chip
<i>pin</i>	GPIO pin number to read from

#### Returns

Value of GPIO pin (usually 0 or 1), negative error code otherwise.

References [L4\\_CV](#).

Referenced by [L4vbus::Gpio\\_pin::get\(\)](#).

Here is the caller graph for this function:



#### 13.8.4.3.5 l4vbus\_gpio\_multi\_config\_pad()

```

int l4vbus_gpio_multi_config_pad (
    l4_cap_idx_t vbus,
    l4vbus_device_handle_t handle,
    unsigned offset,
    unsigned mask,
    unsigned func,
    unsigned value)
  
```

Hardware specific configuration function for multiple GPIO pins.

#### Parameters

<i>vbus</i>	V-BUS capability
<i>handle</i>	Device handle for the GPIO chip
<i>offset</i>	Pin corresponding to the LSB in <i>mask</i> . Note: allowed may be hardware specific.
<i>mask</i>	Mask of GPIO pins to configure. A bit set to 1 configures this pin. A maximum of 32 pins can be configured at once. The real number depends on the hardware and the driver implementation.
<i>func</i>	Hardware specific configuration register, usually offset to the GPIO chip's base address.
<i>value</i>	Value which is written into the hardware specific configuration register for the specified pins

**Returns**

0 if OK, error code otherwise

References [L4\\_CV](#).

Referenced by [L4vbus::Gpio\\_module::config\\_pad\(\)](#).

Here is the caller graph for this function:

**13.8.4.3.6 l4vbus\_gpio\_multi\_get()**

```

int l4vbus_gpio_multi_get (
    l4_cap_idx_t vbus,
    l4vbus_device_handle_t handle,
    unsigned offset,
    unsigned * data)
  
```

Read values of multiple GPIO pins at once.

**Parameters**

	<i>vbus</i>	V-BUS capability
	<i>handle</i>	Device handle for the GPIO chip
	<i>offset</i>	Pin corresponding to the LSB in <i>data</i> . Note: allowed may be hardware specific.
out	<i>data</i>	Each bit returns the value (0 or 1) for the corresponding GPIO pin. The value of pins that are not accessible is undefined.

**Returns**

0 if OK, error code otherwise

References [L4\\_CV](#).

Referenced by [L4vbus::Gpio\\_module::get\(\)](#).

Here is the caller graph for this function:



#### 13.8.4.3.7 l4vbus\_gpio\_multi\_set()

```
int l4vbus_gpio_multi_set (
    l4_cap_idx_t vbus,
    l4vbus_device_handle_t handle,
    unsigned offset,
    unsigned mask,
    unsigned data)
```

Set multiple GPIO output pins at once.

##### Parameters

<i>vbus</i>	V-BUS capability
<i>handle</i>	Device handle for the GPIO chip
<i>offset</i>	Pin corresponding to the LSB in <i>data</i> . Note: allowed may be hardware specific.
<i>mask</i>	Mask of GPIO pins to set. A bit set to 1 selects this pin. A maximum of 32 pins can be set at once. The real number depends on the hardware and the driver implementation.
<i>data</i>	Each bit corresponds to the GPIO pin in <i>mask</i> . The value of each bit is written to the GPIO pin if its bit in <i>mask</i> is set.

##### Returns

0 if OK, error code otherwise

References [L4\\_CV](#).

Referenced by [L4vbus::Gpio\\_module::set\(\)](#).

Here is the caller graph for this function:



#### 13.8.4.3.8 l4vbus\_gpio\_multi\_setup()

```
int l4vbus_gpio_multi_setup (
    l4_cap_idx_t vbus,
    l4vbus_device_handle_t handle,
    unsigned offset,
    unsigned mask,
    unsigned mode,
    unsigned value)
```

Configure function of multiple GPIO pins at once.

#### Parameters

<i>vbus</i>	V-BUS capability
<i>handle</i>	Device handle for the GPIO chip
<i>offset</i>	Pin corresponding to the LSB in <i>mask</i> . Note: allowed may be hardware specific.
<i>mask</i>	Mask of GPIO pins to configure. A bit set to 1 configures this pin. A maximum of 32 pins can be configured at once. The real number depends on the hardware and the driver implementation.
<i>mode</i>	GPIO function, see <a href="#">L4vbus_gpio_generic_func</a> for generic functions. Hardware specific functions must be provided in the lower 8 bits.
<i>value</i>	Optional value to set the GPIO pins to if they are configured as output pins


#### Returns

0 if OK, error code otherwise

References [L4\\_CV](#).

Referenced by [L4vbus::Gpio\\_module::setup\(\)](#).

Here is the caller graph for this function:



#### 13.8.4.3.9 l4vbus\_gpio\_set()

```

int l4vbus_gpio_set (
    l4_cap_idx_t vbus,
    l4vbus_device_handle_t handle,
    unsigned pin,
    int value)
  
```

Set GPIO output pin.

#### Parameters

<i>vbus</i>	V-BUS capability
<i>handle</i>	Device handle for the GPIO chip
<i>pin</i>	GPIO pin number to write to

<i>value</i>	Value to write to the GPIO pin (usually 0 or 1)
--------------	---

**Returns**

0 if OK, error code otherwise

References [L4\\_CV](#).

Referenced by [L4vbus::Gpio\\_pin::set\(\)](#).

Here is the caller graph for this function:

**13.8.4.3.10 l4vbus\_gpio\_setup()**

```

int l4vbus_gpio_setup (
    l4_cap_idx_t vbus,
    l4vbus_device_handle_t handle,
    unsigned pin,
    unsigned mode,
    int value)
  
```

Configure the function of a GPIO pin.

**Parameters**

<i>vbus</i>	V-BUS capability
<i>handle</i>	Device handle for the GPIO chip
<i>pin</i>	GPIO pin number
<i>mode</i>	GPIO function, see <a href="#">L4vbus_gpio_generic_func</a> for generic functions. Hardware specific functions must be provided in the lower 8 bits.
<i>value</i>	Optional value to set the GPIO pin to if it is configured as an output pin



**Returns**

0 if OK, error code otherwise

References [L4\\_CV](#).

Referenced by [L4vbus::Gpio\\_pin::setup\(\)](#).

Here is the caller graph for this function:

**13.8.4.3.11 l4vbus\_gpio\_to\_irq()**

```
int l4vbus_gpio_to_irq (  
    l4_cap_idx_t vbus,  
    l4vbus_device_handle_t handle,  
    unsigned pin)
```

Create IRQ for GPIO pin.

**Parameters**

<i>vbus</i>	V-BUS capability
<i>handle</i>	Device handle for the GPIO chip
<i>pin</i>	GPIO pin to create an IRQ for.

**Returns**

IRQ number if OK, negative error code otherwise

References [L4\\_END\\_DECLS](#).

Referenced by [L4vbus::Gpio\\_pin::to\\_irq\(\)](#).

Here is the caller graph for this function:



### 13.8.5 L4vbus PCI functions

Collaboration diagram for L4vbus PCI functions:



#### Functions

- `L4_BEGIN_DECLS int l4vbus_pci_cfg_read (l4_cap_idx_t vbus, l4vbus_device_handle_t handle, l4_uint32_t bus, l4_uint32_t devfn, l4_uint32_t reg, l4_uint32_t *value, l4_uint32_t width)`  
*Read from the vPCI configuration space using the PCI root bridge.*
- `int l4vbus_pci_cfg_write (l4_cap_idx_t vbus, l4vbus_device_handle_t handle, l4_uint32_t bus, l4_uint32_t devfn, l4_uint32_t reg, l4_uint32_t value, l4_uint32_t width)`  
*Write to the vPCI configuration space using the PCI root bridge.*
- `int l4vbus_pci_irq_enable (l4_cap_idx_t vbus, l4vbus_device_handle_t handle, l4_uint32_t bus, l4_uint32_t devfn, int pin, unsigned char *trigger, unsigned char *polarity)`  
*Enable PCI interrupt for a specific device using the PCI root bridge.*
- `int l4vbus_pcidev_cfg_read (l4_cap_idx_t vbus, l4vbus_device_handle_t handle, l4_uint32_t reg, l4_uint32_t *value, l4_uint32_t width)`  
*Read from the device's vPCI configuration space.*
- `int l4vbus_pcidev_cfg_write (l4_cap_idx_t vbus, l4vbus_device_handle_t handle, l4_uint32_t reg, l4_uint32_t value, l4_uint32_t width)`  
*Write to the device's vPCI configuration space.*
- `int l4vbus_pcidev_irq_enable (l4_cap_idx_t vbus, l4vbus_device_handle_t handle, unsigned char *trigger, unsigned char *polarity)`  
*Enable the device's PCI interrupt.*

#### 13.8.5.1 Detailed Description

#### 13.8.5.2 Function Documentation

##### 13.8.5.2.1 l4vbus\_pci\_cfg\_read()

```

L4_BEGIN_DECLS int l4vbus_pci_cfg_read (
    l4_cap_idx_t vbus,
    l4vbus_device_handle_t handle,
    l4_uint32_t bus,
    l4_uint32_t devfn,
    l4_uint32_t reg,
    l4_uint32_t * value,
    l4_uint32_t width)
  
```

Read from the vPCI configuration space using the PCI root bridge.

**Parameters**

	<i>vbus</i>	Capability of the system bus
	<i>handle</i>	Device handle of the PCI root bridge
	<i>bus</i>	Bus number
	<i>devfn</i>	Device id (upper 16bit) and function (lower 16bit)
	<i>reg</i>	Register in configuration space to read
out	<i>value</i>	Value that has been read
	<i>width</i>	Width to read in bits (e.g. 8, 16, 32)


**Returns**

0 on success, else failure

References [L4\\_CV](#).

Referenced by [L4vbus::Pci\\_host\\_bridge::cfg\\_read\(\)](#).

Here is the caller graph for this function:

**13.8.5.2.2 l4vbus\_pci\_cfg\_write()**

```

int l4vbus_pci_cfg_write (
    l4_cap_idx_t vbus,
    l4vbus_device_handle_t handle,
    l4_uint32_t bus,
    l4_uint32_t devfn,
    l4_uint32_t reg,
    l4_uint32_t value,
    l4_uint32_t width)
  
```

Write to the vPCI configuration space using the PCI root bridge.

**Parameters**

<i>vbus</i>	Capability of the system bus
<i>handle</i>	Device handle of the PCI root bridge

<i>bus</i>	Bus number
<i>devfn</i>	Device id (upper 16bit) and function (lower 16bit)
<i>reg</i>	Register in configuration space to write
<i>value</i>	Value to write
<i>width</i>	Width to write in bits (e.g. 8, 16, 32)

#### Returns

0 on success, else failure

References [L4\\_CV](#).

Referenced by [L4vbus::Pci\\_host\\_bridge::cfg\\_write\(\)](#).

Here is the caller graph for this function:



#### 13.8.5.2.3 l4vbus\_pci\_irq\_enable()

```

int l4vbus_pci_irq_enable (
    l4_cap_idx_t vbus,
    l4vbus_device_handle_t handle,
    l4_uint32_t bus,
    l4_uint32_t devfn,
    int pin,
    unsigned char * trigger,
    unsigned char * polarity)
  
```

Enable PCI interrupt for a specific device using the PCI root bridge.

#### Parameters

	<i>vbus</i>	Capability of the system bus
	<i>handle</i>	Device handle of the PCI root bridge
	<i>bus</i>	Bus number
	<i>devfn</i>	Device id (upper 16bit) and function (lower 16bit)
	<i>pin</i>	Interrupt pin (normally as reported in configuration register INTR)
out	<i>trigger</i>	False if interrupt is level-triggered

out	<i>polarity</i>	True if interrupt is of low polarity
-----	-----------------	--------------------------------------

**Returns**

On success: Interrupt line to be used, else failure

References [L4\\_CV](#).

Referenced by [L4vbus::Pci\\_host\\_bridge::irq\\_enable\(\)](#).

Here is the caller graph for this function:

**13.8.5.2.4 l4vbus\_pciddev\_cfg\_read()**

```

int l4vbus_pciddev_cfg_read (
    l4_cap_idx_t vbus,
    l4vbus_device_handle_t handle,
    l4_uint32_t reg,
    l4_uint32_t * value,
    l4_uint32_t width)

```

Read from the device's vPCI configuration space.

**Parameters**

	<i>vbus</i>	Capability of the system bus
	<i>handle</i>	Device handle of the PCI device
	<i>reg</i>	Register in configuration space to read
out	<i>value</i>	Value that has been read
	<i>width</i>	Width to read in bits (e.g. 8, 16, 32)

**Returns**

0 on success, else failure

References [L4\\_CV](#).

Referenced by [L4vbus::Pci\\_dev::cfg\\_read\(\)](#).

Here is the caller graph for this function:

**13.8.5.2.5 l4vbus\_pciddev\_cfg\_write()**

```
int l4vbus_pciddev_cfg_write (  
    l4_cap_idx_t vbus,  
    l4vbus_device_handle_t handle,  
    l4_uint32_t reg,  
    l4_uint32_t value,  
    l4_uint32_t width)
```

Write to the device's vPCI configuration space.

**Parameters**

<i>vbus</i>	Capability of the system bus
<i>handle</i>	Device handle of the PCI device
<i>reg</i>	Register in configuration space to write
<i>value</i>	Value to write
<i>width</i>	Width to write in bits (e.g. 8, 16, 32)


**Returns**

0 on success, else failure

References [L4\\_CV](#).

Referenced by [L4vbus::Pci\\_dev::cfg\\_write\(\)](#).

Here is the caller graph for this function:



#### 13.8.5.2.6 l4vbus\_pcidev\_irq\_enable()

```

int l4vbus_pcidev_irq_enable (
    l4_cap_idx_t vbus,
    l4vbus_device_handle_t handle,
    unsigned char * trigger,
    unsigned char * polarity)
  
```

Enable the device's PCI interrupt.

##### Parameters

	<i>vbus</i>	Capability of the system bus
	<i>handle</i>	Device handle of the PCI device
out	<i>trigger</i>	False if interrupt is level-triggered
out	<i>polarity</i>	True if interrupt is of low polarity


##### Returns

On success: Interrupt line to be used, else failure

References [L4\\_END\\_DECLS](#).


Referenced by [L4vbus::Pci\\_dev::irq\\_enable\(\)](#).

Here is the caller graph for this function:



### 13.8.6 L4vbus power management functions

Collaboration diagram for L4vbus power management functions:



#### Functions

- [L4\\_BEGIN\\_DECLS](#) `int l4vbus_pm_suspend (l4_cap_idx_t vbus, l4vbus_device_handle_t handle)`  
*Suspend the device.*
- `int l4vbus_pm_resume (l4_cap_idx_t vbus, l4vbus_device_handle_t handle)`  
*Resume the device.*

#### 13.8.6.1 Detailed Description

#### 13.8.6.2 Function Documentation

##### 13.8.6.2.1 l4vbus\_pm\_resume()

```
int l4vbus_pm_resume (
    l4_cap_idx_t vbus,
    l4vbus_device_handle_t handle)
```

Resume the device.

#### Parameters

<i>vbus</i>	V-BUS capability
<i>handle</i>	Handle for the device to be resumed Switches the device from low-power mode to normal operation and restores the saved state.

#### Return values


0	Success.
---	----------

References [L4\\_END\\_DECLS](#).

Referenced by [L4vbus::Pm< DEC >::pm\\_resume\(\)](#).



Here is the caller graph for this function:



#### 13.8.6.2.2 l4vbus\_pm\_suspend()

```
L4_BEGIN_DECLS int l4vbus_pm_suspend (  
    l4_cap_idx_t vbus,  
    l4vbus_device_handle_t handle)
```

Suspend the device.

##### Parameters

<i>vbus</i>	V-BUS capability
<i>handle</i>	Handle for the device to be suspended Saves the state of the device and puts it into a low-power mode.

##### Return values

0	Success.
---	----------

References [L4\\_CV](#).

Referenced by [L4vbus::Pm< DEC >::pm\\_suspend\(\)](#).


Here is the caller graph for this function:



## 13.9 L4Re C Interface

Documentation for the [L4Re C Interface](#).

Collaboration diagram for L4Re C Interface:



### Topics

.

L4Re Util C Interface . . . . .	518
<i>Documentation of the <a href="#">L4 Runtime Environment</a> utility functionality in C.</i>	
•	
Dataspace interface . . . . .	518
<i>Dataspace C interface.</i>	
•	
Debug interface . . . . .	524
•	
DMA Space Interface . . . . .	525
<i>DMA Space C interface.</i>	
•	
Event interface . . . . .	529
<i>Event C interface.</i>	
•	
Log interface . . . . .	532
<i>Log C interface.</i>	
•	
Memory allocator . . . . .	535
<i>Memory allocator C interface.</i>	
•	
Namespace interface . . . . .	540
<i>Namespace C interface.</i>	
•	
Parent interface . . . . .	544
•	
Region map interface . . . . .	544
<i>Region map C interface.</i>	
•	
Capability allocator . . . . .	559
<i>Capability allocator C interface.</i>	
•	
Kumem allocator utility . . . . .	560
<i>Kumem allocator utility C interface.</i>	
•	
Video API . . . . .	561
•	
Initial Environment . . . . .	569
<i>C interface of the initial environment that is provided to an <a href="#">L4</a> task.</i>	

## Files

- file [inhibitor.h](#)  
*Inhibitor C interface.*

### 13.9.1 Detailed Description

Documentation for the [L4Re C Interface](#).


The interface functions closely align with the C++ functions and add no further functionalities.

For new programs it is advised to use the C++ interface.

### 13.9.2 L4Re Util C Interface

Documentation of the [L4](#) Runtime Environment utility functionality in C.

Collaboration diagram for L4Re Util C Interface:



Documentation of the [L4](#) Runtime Environment utility functionality in C.


The interface functions closely align with the C++ functions and add no further functionalities.

For new programs it is advised to use the C++ interface.

### 13.9.3 Dataspace interface

Dataspace C interface.

Collaboration diagram for Dataspace interface:



#### Data Structures

- struct [l4re\\_ds\\_stats\\_t](#)  
*Information about the data space.*

#### Enumerations

- enum [l4re\\_ds\\_map\\_flags](#) { }  
*Flags to specify the memory mapping type of a request.*

## Functions

- [l4\\_ret\\_t l4re\\_ds\\_clear](#) ([l4re\\_ds\\_t](#) ds, [l4re\\_ds\\_offset\\_t](#) offset, [l4re\\_ds\\_size\\_t](#) size) [L4\\_NOTHROW](#)  
*Clear parts of a dataspace.*
- [l4\\_ret\\_t l4re\\_ds\\_allocate](#) ([l4re\\_ds\\_t](#) ds, [l4re\\_ds\\_offset\\_t](#) offset, [l4re\\_ds\\_size\\_t](#) size) [L4\\_NOTHROW](#)  
*Allocate a range in the dataspace.*
- [l4\\_ret\\_t l4re\\_ds\\_copy\\_in](#) ([l4re\\_ds\\_t](#) ds, [l4re\\_ds\\_offset\\_t](#) dst\_offs, [l4re\\_ds\\_t](#) src, [l4re\\_ds\\_offset\\_t](#) src\_offs, [l4re\\_ds\\_size\\_t](#) size) [L4\\_NOTHROW](#)  
*Copy contents from another dataspace.*
- [l4re\\_ds\\_size\\_t l4re\\_ds\\_size](#) ([l4re\\_ds\\_t](#) ds) [L4\\_NOTHROW](#)  
*Get size of a dataspace.*
- [l4re\\_ds\\_flags\\_t l4re\\_ds\\_flags](#) ([l4re\\_ds\\_t](#) ds) [L4\\_NOTHROW](#)  
*Get flags of the dataspace.*
- [l4\\_ret\\_t l4re\\_ds\\_info](#) ([l4re\\_ds\\_t](#) ds, [l4re\\_ds\\_stats\\_t](#) \*stats) [L4\\_NOTHROW](#)  
*Get information on the dataspace.*
- [l4\\_ret\\_t l4re\\_ds\\_map\\_info](#) ([l4re\\_ds\\_t](#) ds, [l4\\_addr\\_t](#) \*start\_addr, [l4\\_addr\\_t](#) \*end\_addr) [L4\\_NOTHROW](#)  
*Get mapping range of dataspace.*

## Variables

- [L4\\_BEGIN\\_DECLS](#) typedef [l4\\_cap\\_idx\\_t](#) [l4re\\_ds\\_t](#)  
*Dataspace type.*

### 13.9.3.1 Detailed Description

Dataspace C interface.

### 13.9.3.2 Enumeration Type Documentation

#### 13.9.3.2.1 l4re\_ds\_map\_flags

```
enum l4re_ds_map_flags
```

Flags to specify the memory mapping type of a request.

## Enumerator

L4RE_DS_F_NORMAL	request normal memory mapping
L4RE_DS_F_CACHEABLE	request normal memory mapping
L4RE_DS_F_BUFFERABLE	request bufferable (write buffered) mappings
L4RE_DS_F_UNCACHEABLE	request uncacheable memory mappings
L4RE_DS_F_CACHING_MASK	mask for caching flags
L4RE_DS_F_CACHING_SHIFT	shift value for caching flags

Definition at line 48 of file [dataspace.h](#).

### 13.9.3.3 Function Documentation

#### 13.9.3.3.1 `l4re_ds_allocate()`

```
l4_ret_t l4re_ds_allocate (
    l4re_ds_t ds,
    l4re_ds_offset_t offset,
    l4re_ds_size_t size)
```

Allocate a range in the dataspace.

##### Parameters

<i>ds</i>	Dataspace capability.
<i>offset</i>	Offset in the dataspace, in bytes.
<i>size</i>	Size of the range, in bytes.

##### Return values

<i>L4_EOK</i>	Success
<i>-L4_ERANGE</i>	Given range is outside the dataspace. (A dataspace provider may also silently ignore areas outside the dataspace.)
<i>-L4_ENOMEM</i>	Not enough memory available.
<i>&lt;0</i>	IPC errors

On success, at least the given range is guaranteed to be allocated. The dataspace manager may also allocate more memory due to page granularity.

The memory is allocated with the same rights as the dataspace capability.

References [L4\\_CV](#), [L4\\_NOTHROW](#), and [l4re\\_ds\\_t](#).

#### 13.9.3.3.2 `l4re_ds_clear()`

```
l4_ret_t l4re_ds_clear (
    l4re_ds_t ds,
    l4re_ds_offset_t offset,
    l4re_ds_size_t size)
```

Clear parts of a dataspace.

##### Parameters

<i>ds</i>	Dataspace capability.
<i>offset</i>	Offset within dataspace (in bytes).
<i>size</i>	Size of region to clear (in bytes).

**Return values**

$\geq 0$	Success.
<code>-L4_ERANGE</code>	Given range is outside the dataspace. (A dataspace provider may also silently ignore areas outside the dataspace.)
<code>-L4_EACCESS</code>	No <a href="#">L4_CAP_FPAGE_W</a> right on dataspace capability.
$< 0$	IPC errors

Zeroes out the memory. Depending on the type of memory the memory could also be deallocated and replaced by a shared zero-page.

References [L4\\_CV](#), [L4\\_NOTHROW](#), and [l4re\\_ds\\_t](#).

**13.9.3.3.3 l4re\_ds\_copy\_in()**

```
l4_ret_t l4re_ds_copy_in (
    l4re_ds_t ds,
    l4re_ds_offset_t dst_offs,
    l4re_ds_t src,
    l4re_ds_offset_t src_offs,
    l4re_ds_size_t size)
```

Copy contents from another dataspace.

**Parameters**

<i>ds</i>	Destination dataspace.
<i>dst_offs</i>	Offset in destination dataspace.
<i>src</i>	Source dataspace to copy from.
<i>src_offs</i>	Offset in the source dataspace.
<i>size</i>	Size to copy (in bytes).

**Return values**

<code>L4_EOK</code>	Success
<code>-L4_EACCESS</code>	No <a href="#">L4_CAP_FPAGE_W</a> right on the destination dataspace.
<code>-L4_EINVAL</code>	Invalid parameter supplied.
$< 0$	IPC errors

The copy operation may use copy-on-write mechanisms. The operation may also fail if both dataspaces are not from the same dataspace manager or the dataspace managers do not cooperate.

References [L4\\_CV](#), [L4\\_NOTHROW](#), and [l4re\\_ds\\_t](#).

#### 13.9.3.3.4 l4re\_ds\_flags()

```
l4re_ds_flags_t l4re_ds_flags (
    l4re_ds_t ds)
```

Get flags of the dataspace.

##### Parameters

<i>ds</i>	Dataspace capability.
-----------	-----------------------

##### Return values

$\geq 0$	Flags of the dataspace
$< 0$	IPC errors

##### See also

[L4Re::Dataspace::F::Flags](#)

References [L4\\_CV](#), [L4\\_NOTHROW](#), and [l4re\\_ds\\_t](#).

#### 13.9.3.3.5 l4re\_ds\_info()

```
l4_ret_t l4re_ds_info (
    l4re_ds_t ds,
    l4re_ds_stats_t * stats)
```

Get information on the dataspace.

##### Parameters

	<i>ds</i>	Dataspace capability.
<i>out</i>	<i>stats</i>	Dataspace information

##### Return values

<i>0</i>	Success
$< 0$	IPC errors

References [L4\\_CV](#), [L4\\_NOTHROW](#), and [l4re\\_ds\\_t](#).



### 13.9.3.3.6 l4re\_ds\_map\_info()

```
l4_ret_t l4re_ds_map_info (
    l4re_ds_t ds,
    l4_addr_t * start_addr,
    l4_addr_t * end_addr)
```

Get mapping range of dataspace.

#### Parameters

<i>ds</i>	Dataspace capability. In case of a MMU-less system, the dataspace must be mapped at the correct address in the task because virtual and physical address must match. This method returns the start and end address of the physically contiguous buffer backing the dataspace.
-----------	---

On MMU-enabled system any page aligned address is permissible. On such systems the method is just a stub.

#### Parameters

out	<i>start_addr</i>	Start address of dataspace.
out	<i>end_addr</i>	End address (inclusive) of dataspace.

#### Return values

>0	Start/end address have been set and need to be obeyed.
0	No constraint of mapping address.
-L4_EPERM	Cannot infer mapping address. Dataspace not mappable.
<0	IPC errors.

References [L4\\_END\\_DECLS](#), [L4\\_NOTHROW](#), and [l4re\\_ds\\_t](#).

### 13.9.3.3.7 l4re\_ds\_size()

```
l4re_ds_size_t l4re_ds_size (
    l4re_ds_t ds)
```

Get size of a dataspace.

#### Parameters

<i>ds</i>	Dataspace capability.
-----------	-----------------------


#### Returns

Size of the dataspace in bytes.

References [L4\\_CV](#), [L4\\_NOTHROW](#), and [l4re\\_ds\\_t](#).

### 13.9.4 Debug interface

Collaboration diagram for Debug interface:



#### Functions

- [L4\\_BEGIN\\_DECLS](#) [l4\\_ret\\_t](#) [l4re\\_debug\\_obj\\_debug](#) ([l4\\_cap\\_idx\\_t](#) *srv*, unsigned long *function*) [L4\\_NOTHROW](#)  
*Call debug function of [L4Re](#) service.*

#### 13.9.4.1 Detailed Description

#### 13.9.4.2 Function Documentation

##### 13.9.4.2.1 [l4re\\_debug\\_obj\\_debug\(\)](#)

```

L4_BEGIN_DECLS l4_ret_t l4re_debug_obj_debug (
    l4_cap_idx_t srv,
    unsigned long function)
  
```

Call debug function of [L4Re](#) service.

#### Parameters

<i>srv</i>	Object to call.
<i>function</i>	Function to call.

#### See also


[L4Re::Debug\\_obj::debug](#)

References [L4\\_END\\_DECLS](#), and [L4\\_NOTHROW](#).

### 13.9.5 DMA Space Interface

DMA Space C interface.

Collaboration diagram for DMA Space Interface:



#### Typedefs

- typedef [l4\\_cap\\_idx\\_t](#) [l4re\\_dma\\_space\\_t](#)  
DMA space capability type.

#### Functions

- [l4\\_ret\\_t](#) [l4re\\_dma\\_space\\_map](#) ([l4re\\_dma\\_space\\_t](#) dma, [l4re\\_ds\\_t](#) src, [l4re\\_ds\\_offset\\_t](#) offset, [l4\\_size\\_t](#) \*size, unsigned long attrs, enum [l4re\\_dma\\_space\\_direction](#) dir, [l4re\\_dma\\_space\\_dma\\_addr\\_t](#) \*dma\_addr) [L4\\_NOTHROW](#)  
Map the given part of this data space into the DMA address space.
- [l4\\_ret\\_t](#) [l4re\\_dma\\_space\\_unmap](#) ([l4re\\_dma\\_space\\_t](#) dma, [l4re\\_dma\\_space\\_dma\\_addr\\_t](#) dma\_addr, [l4\\_size\\_t](#) size, unsigned long attrs, enum [l4re\\_dma\\_space\\_direction](#) dir) [L4\\_NOTHROW](#)  
Unmap the given part of this data space from the DMA address space.
- [l4\\_ret\\_t](#) [l4re\\_dma\\_space\\_associate](#) ([l4re\\_dma\\_space\\_t](#) dma, [l4\\_cap\\_idx\\_t](#) dma\_task, unsigned long attr) [L4\\_NOTHROW](#)  
Associate a (kernel) [DMA space](#) for a device to this *Dma\_space*.
- [l4\\_ret\\_t](#) [l4re\\_dma\\_space\\_disassociate](#) ([l4re\\_dma\\_space\\_t](#) dma)  
Disassociate the (kernel) [DMA space](#) from this *Dma\_space*.

#### 13.9.5.1 Detailed Description

DMA Space C interface.

### 13.9.5.2 Typedef Documentation

#### 13.9.5.2.1 l4re\_dma\_space\_t

```
typedef l4_cap_idx_t l4re_dma_space_t
```

DMA space capability type.

Managed DMA Address Space.

A managed `Dma_space` represents the [L4Re](#) abstraction of an DMA address space of one or several devices. Devices are assigned to a managed `Dma_space` by binding the `Dma_space` to the respective DMA domain (see [L4vbus::Vbus::assign\\_dma\\_domain\(\)](#)), which might link the `Dma_space` with a kernel [DMA space](#). Note that several DMA domains can be bound to the same `Dma_space`. Whenever a device needs direct access to parts of an [L4Re::Dataspace](#), that part of the data space must be mapped to the managed `Dma_space` that is assigned to that device. Binding to DMA domains must happen before mapping. After the DMA accesses to the memory are finished the memory must be unmapped from the device's DMA address space.

Mapping to a managed DMA address space, using `map()`, makes the given parts of the data space visible to the associated device at the returned DMA address. As long as the memory is mapped into a DMA space it is 'pinned' and cannot be subject to dynamic memory management such as swapping. Additionally, `map()` is responsible for the necessary syncing operations before the DMA.

`unmap()` is the reverse operation to `map()` and unmaps the given data-space part for the DMA address space. `unmap()` is responsible for the necessary sync operations after the DMA.

Definition at line 49 of file [dma\\_space.h](#).

### 13.9.5.3 Function Documentation

#### 13.9.5.3.1 l4re\_dma\_space\_associate()

```
l4_ret_t l4re_dma_space_associate (
    l4re_dma_space_t dma,
    l4_cap_idx_t dma_task,
    unsigned long attr)
```

Associate a (kernel) [DMA space](#) for a device to this `Dma_space`.

#### Parameters

	<i>dma</i>	DMA space capability
in	<i>dma_task</i>	The (kernel) <a href="#">DMA space</a> used for the device that shall be associated with this DMA space. In case no IOMMU is present or configured, the <code>dma_task</code> might be an invalid capability when <a href="#">L4Re::Dma_space::Phys_space</a> is set in <code>attr</code> , in this case the CPUs physical memory is used as DMA address space.
in	<i>attr</i>	Attributes for this DMA space. See <a href="#">L4Re::Dma_space::Space_attrb</a> .

#### Return values

---

<code>L4_EOK</code>	Operation successful.
<code>-L4_EPERM</code>	Insufficient permissions; see precondition.
<code>-L4_EINVAL</code>	
<code>-L4_ENOENT</code>	

**Precondition**

The invoked `Dma_space` capability must have the permission [L4\\_CAP\\_FPAGE\\_W](#).

References [L4\\_CV](#), and [L4\\_NOTHROW](#).

**13.9.5.3.2 `l4re_dma_space_disassociate()`**

```
l4_ret_t l4re_dma_space_disassociate (
    l4re_dma_space_t dma)
```

Disassociate the (kernel) [DMA space](#) from this `Dma_space`.

**Parameters**

<code>dma</code>	DMA space capability
------------------	----------------------

**Return values**

<code>L4_EOK</code>	Operation successful.
<code>-L4_EPERM</code>	Insufficient permissions; see precondition.
<code>-L4_ENOENT</code>	

**Precondition**

The invoked `Dma_space` capability must have the permission [L4\\_CAP\\_FPAGE\\_W](#).

References [L4\\_END\\_DECLS](#).

**13.9.5.3.3 `l4re_dma_space_map()`**

```
l4_ret_t l4re_dma_space_map (
    l4re_dma_space_t dma,
    l4re_ds_t src,
    l4re_ds_offset_t offset,
    l4_size_t * size,
    unsigned long attrs,
    enum l4re_dma_space_direction dir,
    l4re_dma_space_dma_addr_t * dma_addr)
```

Map the given part of this data space into the DMA address space.

### Parameters

	<i>dma</i>	DMA space capability
in	<i>src</i>	Source data space (that describes the memory). Caller needs write right to the data space.
in	<i>offset</i>	The offset (bytes) within <i>src</i> .
in, out	<i>size</i>	The size (bytes) of the region to be mapped for DMA, after successful mapping the size returned is the size mapped for DMA as a single block. This size might be smaller than the original input size, in this case the caller might call <code>map()</code> again with a new offset and the remaining size.
in	<i>attrs</i>	The attributes used for this DMA mapping (a combination of <code>Dma_space::Attribute</code> values).
in	<i>dir</i>	The direction of the DMA transfer issued with this mapping. The same value must later be passed to <code>unmap()</code> .
out	<i>dma_addr</i>	The DMA address to use for DMA with the associated device.

### Return values

<i>L4_EOK</i>	Operation successful.
<i>-L4_EPERM</i>	Insufficient permissions; see precondition.
<i>-L4_EINVAL</i>	The capability <i>src</i> is invalid or does not refer to a valid dataspace.
<i>-L4_EEXIST</i>	The specified region overlaps an existing mapping.
<i>-L4_ENOMEM</i>	Not enough memory to allocate internal datastructures.
<i>-L4_ERANGE</i>	<i>offset</i> is larger than the size of the dataspace.

### Precondition

The capability *src* must have the permission [L4\\_CAP\\_FPAGE\\_W](#).

### Note

`associate()` must be called prior to mapping memory. Usually this is done implicitly when binding the managed `Dma_space` to a DMA domain (see [L4vbus::Vbus::assign\\_dma\\_domain\(\)](#)).

References [L4\\_CV](#), [L4\\_NOTHROW](#), and [l4re\\_ds\\_t](#).

#### 13.9.5.3.4 l4re\_dma\_space\_unmap()

```
l4_ret_t l4re_dma_space_unmap (
    l4re_dma_space_t dma,
    l4re_dma_space_dma_addr_t dma_addr,
    l4_size_t size,
    unsigned long attrs,
    enum l4re_dma_space_direction dir)
```

Unmap the given part of this data space from the DMA address space.

**Parameters**

<i>dma</i>	DMA space capability
<i>dma_addr</i>	The DMA address (returned by <code>Dma_space::map()</code> ).
<i>size</i>	The size (bytes) of the memory region to unmap.
<i>attrs</i>	The attributes for the unmap (currently none).
<i>dir</i>	The direction of the finished DMA operation.

**Returns**

0 in the case of success, a negative error code otherwise.

References [L4\\_CV](#), and [L4\\_NOTHROW](#).

**13.9.6 Event interface**

Event C interface.

Collaboration diagram for Event interface:

**Functions**

- [l4\\_ret\\_t l4re\\_event\\_get\\_buffer](#) (const [l4\\_cap\\_idx\\_t](#) server, const [l4re\\_ds\\_t](#) ds) [L4\\_NOTHROW](#)  
*Get an event signal buffer.*
- [l4\\_ret\\_t l4re\\_event\\_get\\_num\\_streams](#) (const [l4\\_cap\\_idx\\_t](#) server) [L4\\_NOTHROW](#)  
*Get number of streams.*
- [l4\\_ret\\_t l4re\\_event\\_get\\_stream\\_info](#) (const [l4\\_cap\\_idx\\_t](#) server, int idx, [l4re\\_event\\_stream\\_info\\_t](#) \*info) [L4\\_NOTHROW](#)  
*Get information on a stream.*
- [l4\\_ret\\_t l4re\\_event\\_get\\_stream\\_info\\_for\\_id](#) (const [l4\\_cap\\_idx\\_t](#) server, [l4\\_umword\\_t](#) stream\_id, [l4re\\_event\\_stream\\_info\\_t](#) \*info) [L4\\_NOTHROW](#)  
*Get info for a stream given a stream id.*
- [l4\\_ret\\_t l4re\\_event\\_get\\_axis\\_info](#) (const [l4\\_cap\\_idx\\_t](#) server, [l4\\_umword\\_t](#) id, unsigned naxes, unsigned const \*axis, [l4re\\_event\\_absinfo\\_t](#) \*info) [L4\\_NOTHROW](#)  
*Get Axis information for a stream.*

**13.9.6.1 Detailed Description**

Event C interface.

### 13.9.6.2 Function Documentation

#### 13.9.6.2.1 l4re\_event\_get\_axis\_info()

```
l4_ret_t l4re_event_get_axis_info (
    const l4_cap_idx_t server,
    l4_umword_t id,
    unsigned naxes,
    unsigned const * axis,
    l4re_event_absinfo_t * info)
```

Get Axis information for a stream.

##### Parameters

	<i>server</i>	Server to talk to.
	<i>id</i>	Id of the stream to get information from.
	<i>naxes</i>	Number of axes in <i>axis</i> array.
in	<i>axis</i>	Array of axis IDs whose information should be retrieved.
out	<i>info</i>	Information buffer to store the retrieved axis infos.

##### Return values

0	Success
<0	Error

##### See also

[L4Re::Event::get\\_axis\\_info](#)

References [L4\\_END\\_DECLS](#), and [L4\\_NOTHROW](#).

#### 13.9.6.2.2 l4re\_event\_get\_buffer()

```
l4_ret_t l4re_event_get_buffer (
    const l4_cap_idx_t server,
    const l4re_ds_t ds)
```

Get an event signal buffer.

##### Parameters

<i>server</i>	Server to talk to.
<i>ds</i>	<a href="#">Buffer</a> to event data.

##### Returns

0 for success, <0 on error

##### See also

[L4Re::Event::get\\_buffer](#)

References [L4\\_CV](#), [L4\\_NOTHROW](#), and [l4re\\_ds\\_t](#).



### 13.9.6.2.3 l4re\_event\_get\_num\_streams()

```
l4_ret_t l4re_event_get_num_streams (
    const l4_cap_idx_t server)
```

Get number of streams.

#### Parameters

<i>server</i>	Server to talk to.
---------------	--------------------

#### Returns

0 for success, <0 on error

#### See also

[L4Re::Event::get\\_num\\_streams](#)

References [L4\\_CV](#), and [L4\\_NOTHROW](#).

### 13.9.6.2.4 l4re\_event\_get\_stream\_info()

```
l4_ret_t l4re_event_get_stream_info (
    const l4_cap_idx_t server,
    int idx,
    l4re_event_stream_info_t * info)
```

Get information on a stream.

#### Parameters

	<i>server</i>	Server to talk to.
	<i>idx</i>	Index value.
out	<i>info</i>	Information buffer.

#### Returns

0 for success, <0 on error

#### See also

[L4Re::Event::get\\_stream\\_info](#)

References [L4\\_CV](#), and [L4\\_NOTHROW](#).

### 13.9.6.2.5 l4re\_event\_get\_stream\_info\_for\_id()

```
l4_ret_t l4re_event_get_stream_info_for_id (
    const l4_cap_idx_t server,
    l4_umword_t stream_id,
    l4re_event_stream_info_t * info)
```

Get info for a stream given a stream id.

#### Parameters

	<i>server</i>	Server to talk to.
	<i>stream_id</i>	Stream ID.
out	<i>info</i>	Information buffer.

#### Returns

0 for success, <0 on error

#### See also


[L4Re::Event::get\\_stream\\_info\\_for\\_id](#)

References [L4\\_CV](#), and [L4\\_NOTHROW](#).

## 13.9.7 Log interface

Log C interface.

Collaboration diagram for Log interface:



#### Functions

- [L4\\_BEGIN\\_DECLS](#) void [l4re\\_log\\_print](#) (char const \*string) [L4\\_NOTHROW](#)  
Write a null terminated string to the default log.
- void [l4re\\_log\\_printn](#) (char const \*string, int len) [L4\\_NOTHROW](#)  
Write a string of a given length to the default log.
- void [l4re\\_log\\_print\\_srv](#) (const [l4\\_cap\\_idx\\_t](#) logcap, char const \*string) [L4\\_NOTHROW](#)  
Write a null terminated string to a log.
- void [l4re\\_log\\_printn\\_srv](#) (const [l4\\_cap\\_idx\\_t](#) logcap, char const \*string, int len) [L4\\_NOTHROW](#)  
Write a string of a given length to a log.

### 13.9.7.1 Detailed Description

Log C interface.

### 13.9.7.2 Function Documentation

#### 13.9.7.2.1 l4re\_log\_print()

```
void l4re_log_print (  
    char const * string) [inline]
```

Write a null terminated string to the default log.

#### Parameters

<i>string</i>	Text to print, null terminated.
---------------	---------------------------------

#### See also

[L4Re::Log::print](#)

Definition at line 81 of file [log.h](#).

References [L4\\_NOTHROW](#), and [l4re\\_log\\_print\\_srv\(\)](#).

Here is the call graph for this function:



#### 13.9.7.2.2 l4re\_log\_print\_srv()

```
void l4re_log_print_srv (  
    const l4\_cap\_idx\_t logcap,  
    char const * string)
```

Write a null terminated string to a log.

#### Parameters

<i>logcap</i>	Log capability (service).
<i>string</i>	Text to print, null terminated.

See also

[L4Re::Log::print](#)

References [L4\\_CV](#), and [L4\\_NOTHROW](#).

Referenced by [l4re\\_log\\_print\(\)](#).

Here is the caller graph for this function:



### 13.9.7.2.3 l4re\_log\_printn()

```
void l4re_log_printn (
    char const * string,
    int len) [inline]
```

Write a string of a given length to the default log.

#### Parameters

<i>string</i>	Text to print, null terminated.
<i>len</i>	Length of string in bytes.

See also

[L4Re::Log::printn](#)

Definition at line 87 of file [log.h](#).

References [L4\\_NOTHROW](#), and [l4re\\_log\\_printn\\_srv\(\)](#).

Here is the call graph for this function:



#### 13.9.7.2.4 l4re\_log\_printn\_srv()

```
void l4re_log_printn_srv (  
    const l4_cap_idx_t logcap,  
    char const * string,  
    int len)
```

Write a string of a given length to a log.

##### Parameters

<i>logcap</i>	Log capability (service).
<i>string</i>	Text to print, null terminated.
<i>len</i>	Length of string in bytes.


##### See also

[L4Re::Log::printn](#)

References [L4\\_CV](#), [L4\\_INLINE](#), and [L4\\_NOTHROW](#).

Referenced by [l4re\\_log\\_printn\(\)](#).

Here is the caller graph for this function:



## 13.9.8 Memory allocator

Memory allocator C interface.

Collaboration diagram for Memory allocator:



## Enumerations

- enum [l4re\\_ma\\_flags](#)  
*Flags for requesting memory at the memory allocator.*

## Functions

- [l4\\_ret\\_t l4re\\_ma\\_alloc](#) (long size, [l4re\\_ds\\_t](#) const mem, unsigned long flags) [L4\\_NOTHROW](#)  
*Allocate memory.*
- [l4\\_ret\\_t l4re\\_ma\\_alloc\\_align](#) (long size, [l4re\\_ds\\_t](#) const mem, unsigned long flags, unsigned long align) [L4\\_NOTHROW](#)  
*Allocate memory.*
- [l4\\_ret\\_t l4re\\_ma\\_alloc\\_align\\_srv](#) ([l4\\_cap\\_idx\\_t](#) srv, long size, [l4re\\_ds\\_t](#) const mem, unsigned long flags, unsigned long align) [L4\\_NOTHROW](#)  
*Allocate memory.*

### 13.9.8.1 Detailed Description

Memory allocator C interface.

### 13.9.8.2 Enumeration Type Documentation

#### 13.9.8.2.1 l4re\_ma\_flags

enum [l4re\\_ma\\_flags](#)

Flags for requesting memory at the memory allocator.

See also

[L4Re::Mem\\_alloc::Mem\\_alloc\\_flags](#)

Definition at line 32 of file [mem\\_alloc.h](#).

### 13.9.8.3 Function Documentation

#### 13.9.8.3.1 l4re\_ma\_alloc()

```
l4_ret_t l4re_ma_alloc (
    long size,
    l4re_ds_t const mem,
    unsigned long flags) [inline]
```

Allocate memory.

**Parameters**

<i>size</i>	Size in bytes to be requested. Allocation granularity is (super)pages, however, the allocator will store the byte-granular given size as the size of the dataspace and consecutively will use this byte-granular size for servicing the dataspace. Allocators may optionally also implement a maximum allocation strategy: if <i>size</i> is a negative value and <i>flags</i> set the <code>Mem_alloc_flags::Continuous</code> bit, the allocator tries to allocate as much memory as possible leaving an amount of at least <code>-size</code> bytes within the associated quota.
<i>mem</i>	Capability slot where the capability to the dataspace is received.
<i>flags</i>	Special dataspace properties, see <a href="#">l4re_ma_flags</a>

**Return values**

<i>0</i>	Success
<i>-L4_ERANGE</i>	Given size not supported.
<i>-L4_ENOMEM</i>	Not enough memory available.
<i>&lt; 0</i>	IPC error

**See also**

[L4Re::Mem\\_alloc::alloc](#)

The memory allocator returns a dataspace.

**Note**

This function is using the [L4Re::Env::env\(\)->mem\\_alloc\(\)](#) service.

**Examples**

[examples/libs/l4re/c/ma+rm.c](#).

Definition at line 136 of file [mem\\_alloc.h](#).

References [L4\\_NOTHROW](#), [l4re\\_ds\\_t](#), and [l4re\\_ma\\_alloc\\_align\\_srv\(\)](#).

Here is the call graph for this function:



### 13.9.8.3.2 l4re\_ma\_alloc\_align()

```
l4_ret_t l4re_ma_alloc_align (
    long size,
    l4re_ds_t const mem,
    unsigned long flags,
    unsigned long align) [inline]
```

Allocate memory.

#### Parameters

<i>size</i>	Size in bytes to be requested. Allocation granularity is (super)pages, however, the allocator will store the byte-granular given size as the size of the dataspace and consecutively will use this byte-granular size for servicing the dataspace. Allocators may optionally also implement a maximum allocation strategy: if <i>size</i> is a negative value and <i>flags</i> set the <code>Mem_alloc_flags::Continuous</code> bit, the allocator tries to allocate as much memory as possible leaving an amount of at least <code>-size</code> bytes within the associated quota.
<i>mem</i>	Capability slot where the capability to the dataspace is received.
<i>flags</i>	Special dataspace properties, see <a href="#">l4re_ma_flags</a>
<i>align</i>	Log2 alignment of dataspace if supported by allocator, will be at least <code>L4_PAGESHIFT</code> , with <code>Super_pages</code> flag set at least <code>L4_SUPERPAGESHIFT</code>

#### Return values

<code>0</code>	Success
<code>-L4_ERANGE</code>	Given size not supported.
<code>-L4_ENOMEM</code>	Not enough memory available.
<code>&lt;0</code>	IPC error

#### See also

[L4Re::Mem\\_alloc::alloc](#) and  
[l4re\\_ma\\_alloc](#)

The memory allocator returns a dataspace.

#### Note

This function is using the [L4Re::Env::env\(\)](#)->`mem_alloc()` service.

Definition at line 144 of file [mem\\_alloc.h](#).

References [L4\\_NOTHROW](#), [l4re\\_ds\\_t](#), and [l4re\\_ma\\_alloc\\_align\\_srv\(\)](#).



Here is the call graph for this function:



### 13.9.8.3.3 l4re\_ma\_alloc\_align\_srv()

```

l4_ret_t l4re_ma_alloc_align_srv (
    l4_cap_idx_t srv,
    long size,
    l4re_ds_t const mem,
    unsigned long flags,
    unsigned long align)
  
```

Allocate memory.

#### Parameters

<i>srv</i>	Memory allocator service.
<i>size</i>	Size to be requested.
<i>mem</i>	Capability slot to put the requested dataspace in
<i>flags</i>	Flags, see <a href="#">l4re_ma_flags</a>
<i>align</i>	Log2 alignment of dataspace if supported by allocator, will be at least L4_PAGESHIFT, with Super_↔ pages flag set at least L4_SUPERPAGESHIFT, default 0

#### Returns

0 on success, <0 on error

#### See also


[L4Re::Mem\\_alloc::alloc](#)

The memory allocator returns a dataspace.

References [L4\\_CV](#), [L4\\_INLINE](#), [L4\\_NOTHROW](#), and [l4re\\_ds\\_t](#).

Referenced by [l4re\\_ma\\_alloc\(\)](#), and [l4re\\_ma\\_alloc\\_align\(\)](#).

Here is the caller graph for this function:



### 13.9.9 Namespace interface

Namespace C interface.

Collaboration diagram for Namespace interface:



#### Enumerations

- enum `l4re_ns_register_flags`  
*Namespace register flags.*

#### Functions

- `l4_ret_t l4re_ns_query_to_srv (l4re_namespace_t srv, char const *name, l4_cap_idx_t const cap, int timeout)`  
`L4_NOTHROW`  
*Query the name space for the object named by `name`.*
- `l4_ret_t l4re_ns_query_srv (l4re_namespace_t srv, char const *name, l4_cap_idx_t const cap)`  
`L4_NOTHROW`  
*Query the name space for the object named by `name`.*
- `l4_ret_t l4re_ns_register_obj_srv (l4re_namespace_t srv, char const *name, l4_cap_idx_t const obj, unsigned flags)`  
`L4_NOTHROW`  
*Register an object with a name.*

#### Variables

- `L4_BEGIN_DECLS` typedef `l4_cap_idx_t l4re_namespace_t`  
*Namespace type.*

### 13.9.9.1 Detailed Description

Namespace C interface.

### 13.9.9.2 Enumeration Type Documentation

#### 13.9.9.2.1 l4re\_ns\_register\_flags

```
enum l4re_ns_register_flags
```

Namespace register flags.

See also

[L4Re::Namespace::Register\\_flags](#)

Definition at line 29 of file [namespace.h](#).

### 13.9.9.3 Function Documentation

#### 13.9.9.3.1 l4re\_ns\_query\_srv()

```
l4_ret_t l4re_ns_query_srv (
    l4re_namespace_t srv,
    char const * name,
    l4_cap_idx_t const cap) [inline]
```

Query the name space for the object named by *name*.

#### Parameters

<i>srv</i>	Name space server to use for the query.
<i>name</i>	String to query.
<i>cap</i>	Capability slot where the received capability will be stored.


#### Return values

<i>0</i>	Name could be fully resolved.
<i>&gt;0</i>	Name could only be partly resolved. The number of remaining characters is returned.
<i>-L4_ENOENT</i>	Entry could not be found.
<i>-L4_EAGAIN</i>	Entry exists but no object is yet attached. Try again later.
<i>&lt;0</i>	IPC errors, see <a href="#">l4_error_code_t</a> .

Definition at line 95 of file [namespace.h](#).

References [L4\\_NOTHROW](#), [l4re\\_namespace\\_t](#), and [l4re\\_ns\\_query\\_to\\_srv\(\)](#).

Here is the call graph for this function:



### 13.9.9.3.2 l4re\_ns\_query\_to\_srv()

```

l4_ret_t l4re_ns_query_to_srv (
    l4re_namespace_t srv,
    char const * name,
    l4_cap_idx_t const cap,
    int timeout)
  
```

Query the name space for the object named by `name`.

#### Parameters

<i>timeout</i>	Timeout of query in milliseconds. The client will only wait if a name already has been registered with the server but no object has been attached yet.
<i>srv</i>	Name space server to use for the query.
<i>name</i>	String to query.
<i>cap</i>	Capability slot where the received capability will be stored.


#### Return values

<i>0</i>	Name could be fully resolved.
<i>&gt;0</i>	Name could only be partly resolved. The number of remaining characters is returned.
<i>-L4_ENOENT</i>	Entry could not be found.
<i>-L4_EAGAIN</i>	Entry exists but no object is yet attached. Try again later.
<i>&lt;0</i>	IPC errors, see <a href="#">l4_error_code_t</a> .

References [L4\\_CV](#), [L4\\_INLINE](#), [L4\\_NOTHROW](#), and [l4re\\_namespace\\_t](#).

Referenced by [l4re\\_ns\\_query\\_srv\(\)](#).

Here is the caller graph for this function:



### 13.9.9.3.3 l4re\_ns\_register\_obj\_srv()

```

l4_ret_t l4re_ns_register_obj_srv (
    l4re_namespace_t srv,
    char const * name,
    l4_cap_idx_t const obj,
    unsigned flags)
  
```

Register an object with a name.

#### Parameters

<i>srv</i>	Name space server to use for the query.
<i>name</i>	Name under which the object should be registered.
<i>obj</i>	Capability to object to register. An invalid capability may be given to only reserve the name for later use.
<i>flags</i>	Flags to assign to the entry, see <a href="#">L4Re::Namespace::Register_flags</a> . Note that the rights that are assigned to a capability are not only determined by the rights given in these flags but also by the rights with which the <code>obj</code> capability was mapped to the name space.

#### Return values

<i>0</i>	Object was successfully registered with <i>name</i> .
<i>-L4_EEXIST</i>	Name already registered.
<i>-L4_EPERM</i>	Insufficient permissions; see precondition.
<i>-L4_ENOMEM</i>	Server has insufficient resources.
<i>-L4_EINVAL</i>	Invalid parameter.
<i>&lt;0</i>	IPC errors, see <a href="#">l4_error_code_t</a> .


#### Precondition

The invoked Namespace capability must have the permission [L4\\_CAP\\_FPAGE\\_W](#).

References [L4\\_CV](#), [L4\\_INLINE](#), [L4\\_NOTHROW](#), and [l4re\\_namespace\\_t](#).

### 13.9.10 Parent interface

Collaboration diagram for Parent interface:



### 13.9.11 Region map interface

Region map C interface.

Collaboration diagram for Region map interface:



### Enumerations

- enum `l4re_rm_flags_values` {  
`L4RE_RM_F_R` = `L4RE_DS_F_R` , `L4RE_RM_F_W` = `L4RE_DS_F_W` , `L4RE_RM_F_X` = `L4RE_DS_F_X`  
, `L4RE_RM_F_RX` = `L4RE_DS_F_RX` ,  
`L4RE_RM_F_RW` = `L4RE_DS_F_RW` , `L4RE_RM_F_RWX` = `L4RE_DS_F_RWX` , `L4RE_RM_F_KERNEL`  
= `0x100` , `L4RE_RM_F_DETACH_FREE` = `0x200` ,  
`L4RE_RM_F_PAGER` = `0x400` , `L4RE_RM_F_RESERVED` = `0x800` , `L4RE_RM_CACHING_SHIFT` = `4` ,  
`L4RE_RM_F_CACHING` = `L4RE_DS_F_CACHING_MASK` ,  
`L4RE_RM_REGION_FLAGS` = `0xffff` , `L4RE_RM_F_CACHE_NORMAL` = `L4RE_DS_F_NORMAL` ,  
`L4RE_RM_F_CACHE_BUFFERED` = `L4RE_DS_F_BUFFERABLE` , `L4RE_RM_F_CACHE_UNCACHED`  
= `L4RE_DS_F_UNCACHEABLE` ,  
`L4RE_RM_F_SEARCH_ADDR` = `0x020000` , `L4RE_RM_F_IN_AREA` = `0x040000` , `L4RE_RM_F_EAGER_MAP`  
= `0x080000` , `L4RE_RM_F_NO_EAGER_MAP` = `0x100000` ,  
`L4RE_RM_F_ATTACH_FLAGS` = `0x1f0000` }

*Flags for region operations.*

## Functions

- `int l4re_rm_reserve_area (l4_addr_t *start, unsigned long size, l4re_rm_flags_t flags, unsigned char align) L4_NOTHROW`  
*Reserve the given area in the region map.*
- `int l4re_rm_free_area (l4_addr_t addr) L4_NOTHROW`  
*Free an area from the region map.*
- `int l4re_rm_attach (void **start, unsigned long size, l4re_rm_flags_t flags, l4re_ds_t mem, l4re_rm_offset_t offs, unsigned char align) L4_NOTHROW`  
*Attach a data space to a region.*
- `int l4re_rm_detach (void *addr) L4_NOTHROW`  
*Detach and unmap a region from the address space in the current task.*
- `int l4re_rm_detach_ds (void *addr, l4re_ds_t *ds) L4_NOTHROW`  
*Detach and unmap a region and return affected dataspace in the current task.*
- `int l4re_rm_detach_unmap (l4_addr_t addr, l4_cap_idx_t task) L4_NOTHROW`  
*Detach and unmap in specified task.*
- `int l4re_rm_detach_ds_unmap (void *addr, l4re_ds_t *ds, l4_cap_idx_t task) L4_NOTHROW`  
*Detach and unmap in specified task.*
- `int l4re_rm_find (l4_addr_t *addr, unsigned long *size, l4re_rm_offset_t *offset, l4re_rm_flags_t *flags, l4re_ds_t *m) L4_NOTHROW`  
*Find a region given an address and size.*
- `int l4re_rm_get_info (l4_addr_t addr, char *name, unsigned int len, l4re_rm_offset_t *backing_offset) L4_NOTHROW`  
*Return auxiliary information of a region.*
- `void l4re_rm_show_lists (void) L4_NOTHROW`  
*Dump region map internal data structures.*
- `int l4re_rm_reserve_area_srv (l4_cap_idx_t rm, l4_addr_t *start, unsigned long size, l4re_rm_flags_t flags, unsigned char align) L4_NOTHROW`
- `int l4re_rm_free_area_srv (l4_cap_idx_t rm, l4_addr_t addr) L4_NOTHROW`
- `int l4re_rm_attach_srv (l4_cap_idx_t rm, void **start, unsigned long size, l4re_rm_flags_t flags, l4re_ds_t mem, l4re_rm_offset_t offs, unsigned char align) L4_NOTHROW`
- `int l4re_rm_detach_srv (l4_cap_idx_t rm, l4_addr_t addr, l4re_ds_t *ds, l4_cap_idx_t task) L4_NOTHROW`
- `int l4re_rm_find_srv (l4_cap_idx_t rm, l4_addr_t *addr, unsigned long *size, l4re_rm_offset_t *offset, l4re_rm_flags_t *flags, l4re_ds_t *m) L4_NOTHROW`
- `int l4re_rm_get_info_srv (l4_cap_idx_t rm, l4_addr_t addr, char *name, unsigned int len, l4re_rm_offset_t *backing_offset) L4_NOTHROW`
- `void l4re_rm_show_lists_srv (l4_cap_idx_t rm) L4_NOTHROW`  
*Dump region map internal data structures.*

### 13.9.11.1 Detailed Description

Region map C interface.

### 13.9.11.2 Enumeration Type Documentation

#### 13.9.11.2.1 l4re\_rm\_flags\_values

```
enum l4re_rm_flags_values
```

Flags for region operations.

**Enumerator**

L4RE_RM_F_R	Region is read-only.
L4RE_RM_F_KERNEL	Kernel-provided memory (KUMEM).
L4RE_RM_F_DETACH_FREE	Free the portion of the data space after detach.
L4RE_RM_F_PAGER	Region has a pager.
L4RE_RM_F_RESERVED	Region is reserved (blocked).
L4RE_RM_CACHING_SHIFT	Start of region mapper cache bits.
L4RE_RM_F_CACHING	Mask of all region manager cache bits.
L4RE_RM_REGION_FLAGS	Mask of all region flags.
L4RE_RM_F_CACHE_NORMAL	Cache bits for normal cacheable memory.
L4RE_RM_F_CACHE_BUFFERED	Cache bits for buffered (write combining) memory.
L4RE_RM_F_CACHE_UNCACHED	Cache bits for uncached memory.
L4RE_RM_F_SEARCH_ADDR	Search for a suitable address range.
L4RE_RM_F_IN_AREA	Search only in area, or map into area.
L4RE_RM_F_EAGER_MAP	Eagerly map the attached data space in.
L4RE_RM_F_NO_EAGER_MAP	Prevent eager mapping of the attached data space.
L4RE_RM_F_ATTACH_FLAGS	Mask of all attach flags.

Definition at line 30 of file [rm.h](#).

**13.9.11.3 Function Documentation****13.9.11.3.1 l4re\_rm\_attach()**

```
int l4re_rm_attach (
    void ** start,
    unsigned long size,
    l4re_rm_flags_t flags,
    l4re_ds_t mem,
    l4re_rm_offset_t offs,
    unsigned char align) [inline]
```

Attach a data space to a region.

**Parameters**

in, out	<i>start</i>	Virtual start address where the region manager shall attach the data space. Will be rounded down to the nearest start of a page. If <a href="#">L4Re::Rm::F::Search_addr</a> is given this value is used as the start address to search for a free virtual memory region and the resulting address is returned here. If <a href="#">L4Re::Rm::F::In_area</a> is given the value is used as a selector for the area (see <a href="#">L4Re::Rm::reserve_area</a> ) to attach the data space to.
	<i>size</i>	Size of the data space to attach (in bytes). Will be rounded up to the nearest multiple of the page size.



	<i>flags</i>	The flags control how and with which rights the dataspace is attached to the region. See <a href="#">L4Re::Rm::F::Attach_flags</a> and <a href="#">L4Re::Rm::F::Region_flags</a> . The caller must specify the desired rights of the attached region explicitly. The default set of rights is empty. If the <code>F : ↔ Eager_map</code> flag is set this function may also return <a href="#">L4Re::Dataspace::map</a> error codes if the mapping fails.
	<i>mem</i>	Data space.
	<i>offs</i>	Offset into the data space to use.
	<i>align</i>	Alignment of the virtual region, log2-size, default: a page ( <a href="#">L4_PAGESHIFT</a> ). This is only meaningful if the <a href="#">L4Re::Rm::F::Search_addr</a> flag is used.

### Return values

0	Success
-L4_ENOENT	No area could be found (see <a href="#">L4Re::Rm::F::In_area</a> )
-L4_EPERM	Operation not allowed.
-L4_EINVAL	
-L4_EADDRNOTAVAIL	The given address is not available.
<0	IPC errors

Makes the whole or parts of a data space visible in the virtual memory of the corresponding task. The corresponding region in the virtual address space is backed with the contents of the dataspace.

### Note

When searching for a free place in the virtual address space, the space between *start* and the end of the virtual address space is

### See also

[L4Re::Rm::attach](#)

This function is using the `L4::Env::env()->rm()` service.

### Examples

[examples/libs/l4re/c/ma+rm.c](#).

Definition at line 342 of file [rm.h](#).

References [L4\\_NOTHROW](#), [l4re\\_ds\\_t](#), and [l4re\\_rm\\_attach\\_srv\(\)](#).

Here is the call graph for this function:



### 13.9.11.3.2 l4re\_rm\_attach\_srv()

```
int l4re_rm_attach_srv (
    l4_cap_idx_t rm,
    void ** start,
    unsigned long size,
    l4re_rm_flags_t flags,
    l4re_ds_t mem,
    l4re_rm_offset_t offs,
    unsigned char align)
```


See also

[L4Re::Rm::attach](#)

References [L4\\_CV](#), [L4\\_NOTHROW](#), and [l4re\\_ds\\_t](#).

Referenced by [l4re\\_rm\\_attach\(\)](#).

Here is the caller graph for this function:



### 13.9.11.3.3 l4re\_rm\_detach()

```
int l4re_rm_detach (
    void * addr) [inline]
```

Detach and unmap a region from the address space in the current task.

#### Parameters

<i>addr</i>	Address of the region to detach.
-------------	----------------------------------

#### Return values

<a href="#">L4Re::Rm::Detach_result</a>	On success.
<code>-L4_ENOENT</code>	No region found.
<code>&lt;0</code>	IPC errors

Frees a region in the virtual address space given by *addr*. The corresponding part of the address space is now available again.

Also

See also

[L4Re::Rm::detach](#)

This function is using the `L4::Env::env()->rm()` service.

Definition at line 352 of file [rm.h](#).

References [L4\\_BASE\\_TASK\\_CAP](#), [L4\\_NOTHROW](#), and [l4re\\_rm\\_detach\\_srv\(\)](#).

Here is the call graph for this function:



#### 13.9.11.3.4 l4re\_rm\_detach\_ds()

```
int l4re_rm_detach_ds (
    void * addr,
    l4re_ds_t * ds) [inline]
```

Detach and unmap a region and return affected dataspace in the current task.

##### Parameters

	<i>addr</i>	Address of the region to detach.
out	<i>ds</i>	Returns dataspace that is affected.

##### Return values

<a href="#">L4Re::Rm::Detach_result</a>	On success.
<code>-L4_ENOENT</code>	No region found.
<code>&lt;0</code>	IPC errors

Frees a region in the virtual address space given by *addr*. The corresponding part of the address space is now available again.

Also

See also

[L4Re::Rm::detach](#)

This function is using the `L4::Env::env()->rm()` service.


Examples

[examples/libs/l4re/c/ma+rm.c](#).

Definition at line 365 of file [rm.h](#).

References [L4\\_BASE\\_TASK\\_CAP](#), [L4\\_NOTHROW](#), [l4re\\_ds\\_t](#), and [l4re\\_rm\\_detach\\_srv\(\)](#).

Here is the call graph for this function:



### 13.9.11.3.5 l4re\_rm\_detach\_ds\_unmap()

```

int l4re_rm_detach_ds_unmap (
    void * addr,
    l4re_ds_t * ds,
    l4_cap_idx_t task) [inline]
  
```

Detach and unmap in specified task.

#### Parameters

	<i>addr</i>	Address of the region to detach.
out	<i>ds</i>	Returns dataspace that is affected.
	<i>task</i>	Task to unmap pages from, specify <code>L4_INVALID_CAP</code> to not unmap

#### Returns

0 on success, <0 on error

Also

See also

[L4Re::Rm::detach](#)

This function is using the `L4::Env::env()->rm()` service.

Definition at line 372 of file `rm.h`.

References [L4\\_NOTHROW](#), [l4re\\_ds\\_t](#), and [l4re\\_rm\\_detach\\_srv\(\)](#).

Here is the call graph for this function:



### 13.9.11.3.6 l4re\_rm\_detach\_srv()

```

int l4re_rm_detach_srv (
    l4_cap_idx_t rm,
    l4_addr_t addr,
    l4re_ds_t * ds,
    l4_cap_idx_t task)
  
```


See also

[L4Re::Rm::detach](#)

References [L4\\_CV](#), [L4\\_NOTHROW](#), and [l4re\\_ds\\_t](#).

Referenced by [l4re\\_rm\\_detach\(\)](#), [l4re\\_rm\\_detach\\_ds\(\)](#), [l4re\\_rm\\_detach\\_ds\\_unmap\(\)](#), and [l4re\\_rm\\_detach\\_unmap\(\)](#).

Here is the caller graph for this function:



### 13.9.11.3.7 l4re\_rm\_detach\_unmap()

```
int l4re_rm_detach_unmap (
    l4_addr_t addr,
    l4_cap_idx_t task) [inline]
```

Detach and unmap in specified task.

#### Parameters

<i>addr</i>	Address of the region to detach.
<i>task</i>	Task to unmap pages from, specify L4_INVALID_CAP to not unmap

#### Returns

0 on success, <0 on error

Also

See also

[L4Re::Rm::detach](#)

This function is using the `L4::Env::env()->rm()` service.

Definition at line 359 of file [rm.h](#).

References [L4\\_NOTHROW](#), and [l4re\\_rm\\_detach\\_srv\(\)](#).

Here is the call graph for this function:



### 13.9.11.3.8 l4re\_rm\_find()

```
int l4re_rm_find (
    l4_addr_t * addr,
    unsigned long * size,
    l4re_rm_offset_t * offset,
    l4re_rm_flags_t * flags,
    l4re_ds_t * m) [inline]
```

Find a region given an address and size.


## Parameters

in, out	<i>addr</i>	Address to look for. Returns the start address of the found region.
in, out	<i>size</i>	Size of the area to look for (in bytes). Returns the size of the found region (in bytes).
out	<i>offset</i>	Offset at the beginning of the region within the associated dataspace.
out	<i>flags</i>	Region flags, see <code>F::Region_flags</code> (and <code>F::In_area</code> ).
out	<i>m</i>	Associated dataspace or paging service.

## Return values

0	Success
-L4_EPERM	Operation not allowed.
-L4_ENOENT	No region found.
<0	IPC errors

This function returns the properties of the region that contains the area described by the `addr` and `size` parameter. If no such region is found but a reserved area, the area is returned and `F::In_area` is set in `flags`. Note, in the case of an area the `offset` and `m` return values are invalid.



## Note

The value of the `size` input parameter should be 1 to assure that a region can be determined unambiguously.

## See also

[L4Re::Rm::find](#)

Definition at line 379 of file [rm.h](#).

References [L4\\_NOTHROW](#), [l4re\\_ds\\_t](#), and [l4re\\_rm\\_find\\_srv\(\)](#).

Here is the call graph for this function:



### 13.9.11.3.9 l4re\_rm\_find\_srv()

```
int l4re_rm_find_srv (
    l4_cap_idx_t rm,
    l4_addr_t * addr,
    unsigned long * size,
    l4re_rm_offset_t * offset,
    l4re_rm_flags_t * flags,
    l4re_ds_t * m)
```

See also

[L4Re::Rm::find](#)

References [L4\\_CV](#), [L4\\_NOTHROW](#), and [l4re\\_ds\\_t](#).

Referenced by [l4re\\_rm\\_find\(\)](#).

Here is the caller graph for this function:



### 13.9.11.3.10 l4re\_rm\_free\_area()

```
int l4re_rm_free_area (
    l4_addr_t addr) [inline]
```

Free an area from the region map.

#### Parameters

<i>addr</i>	An address within the area to free.
-------------	-------------------------------------

#### Return values

0	Success
-L4_ENOENT	No area found.
<0	IPC errors



**Note**

The data spaces that are attached to that area are not detached by this operation.

**See also**

`reserve_area()` for more information about areas.


[L4Re::Rm::free\\_area](#)

This function is using the `L4::Env::env()->rm()` service.

Definition at line 336 of file [rm.h](#).

References [L4\\_NOTHROW](#), and [l4re\\_rm\\_free\\_area\\_srv\(\)](#).

Here is the call graph for this function:

**13.9.11.3.11 l4re\_rm\_free\_area\_srv()**

```
int l4re_rm_free_area_srv (  
    l4_cap_idx_t rm,  
    l4_addr_t addr)
```

**See also**

[L4Re::Rm::free\\_area](#)

References [L4\\_CV](#), and [L4\\_NOTHROW](#).

Referenced by [l4re\\_rm\\_free\\_area\(\)](#).

Here is the caller graph for this function:



### 13.9.11.3.12 l4re\_rm\_get\_info()

```
int l4re_rm_get_info (
    l4_addr_t addr,
    char * name,
    unsigned int len,
    l4re_rm_offset_t * backing_offset) [inline]
```

Return auxiliary information of a region.

This is a debugging feature and might not be available.

#### Parameters

	<i>addr</i>	Virtual address of the region.
out	<i>name</i>	Name of the region.
out	<i>backing_offset</i>	Backing offset information.

#### Return values

0	Success
-L4_ENOENT	Region not found.
-L4_ENOSYS	Function not available.
<0	IPC errors

#### Parameters

<i>len</i>	Length of the name given in name argument, in bytes.
------------	--

#### See also

[L4Re::Rm::get\\_info](#)

Definition at line 395 of file [rm.h](#).

References [L4\\_NOTHROW](#), and [l4re\\_rm\\_get\\_info\\_srv\(\)](#).

Here is the call graph for this function:



### 13.9.11.3.13 l4re\_rm\_get\_info\_srv()

```
int l4re_rm_get_info_srv (
    l4_cap_idx_t rm,
    l4_addr_t addr,
    char * name,
    unsigned int len,
    l4re_rm_offset_t * backing_offset)
```


See also

[L4Re::Rm::get\\_info](#)

References [L4\\_CV](#), and [L4\\_NOTHROW](#).

Referenced by [l4re\\_rm\\_get\\_info\(\)](#).

Here is the caller graph for this function:



### 13.9.11.3.14 l4re\_rm\_reserve\_area()

```
int l4re_rm_reserve_area (
    l4_addr_t * start,
    unsigned long size,
    l4re_rm_flags_t flags,
    unsigned char align) [inline]
```

Reserve the given area in the region map.

#### Parameters

in, out	<i>start</i>	The virtual start address of the area to reserve. Returns the start address of the area.
	<i>size</i>	The size of the area to reserve (in bytes).
	<i>flags</i>	Flags for the reserved area (see <a href="#">L4Re::Rm::F::Region_flags</a> and <a href="#">L4Re::Rm::F::Attach_flags</a> ).
	<i>align</i>	Alignment of area if searched as bits (log2 value).

#### Return values

0	Success
-L4_EADDRNOTAVAIL	The given area cannot be reserved.
<0	IPC errors

This function reserves an area within the virtual address space managed by the region map. There are two kinds of areas available:

- Reserved areas (*flags* = [L4Re::Rm::F::Reserved](#)), where no data spaces can be attached
- Special purpose areas (*flags* = 0), where data spaces can be attached to the area via the [L4Re::Rm::F::In\\_area](#) flag and a start address within the area itself.

#### Note

When searching for a free place in the virtual address space (with *flags* = [L4Re::Rm::F::Search\\_addr](#)), the space between *start* and the end of the virtual address space is searched.

#### See also

[L4Re::Rm::reserve\\_area](#)

This function is using the `L4::Env::env()->rm()` service.

Definition at line 328 of file [rm.h](#).

References [L4\\_NOTHROW](#), and [l4re\\_rm\\_reserve\\_area\\_srv\(\)](#).

Here is the call graph for this function:



#### 13.9.11.3.15 l4re\_rm\_reserve\_area\_srv()

```

int l4re_rm_reserve_area_srv (
    l4_cap_idx_t rm,
    l4_addr_t * start,
    unsigned long size,
    l4re_rm_flags_t flags,
    unsigned char align)
  
```

See also

[L4Re::Rm::reserve\\_area](#)

References [L4\\_CV](#), and [L4\\_NOTHROW](#).

Referenced by [l4re\\_rm\\_reserve\\_area\(\)](#).

Here is the caller graph for this function:



#### 13.9.11.3.16 l4re\_rm\_show\_lists()

```
void l4re_rm_show_lists (
    void ) [inline]
```

Dump region map internal data structures.

This function is using the `L4::Env::env()->rm()` service.

Definition at line 387 of file [rm.h](#).

References [L4\\_NOTHROW](#), and [l4re\\_rm\\_show\\_lists\\_srv\(\)](#).


Here is the call graph for this function:



### 13.9.12 Capability allocator

Capability allocator C interface.

Collaboration diagram for Capability allocator:



## Functions

- [L4\\_BEGIN\\_DECLS](#) [l4\\_cap\\_idx\\_t](#) **l4re\_util\_cap\_alloc** (void) [L4\\_NOTHROW](#)  
*Get free capability index at capability allocator.*
- void **l4re\_util\_cap\_free** ([l4\\_cap\\_idx\\_t](#) cap) [L4\\_NOTHROW](#)  
*Return capability index to capability allocator.*
- void **l4re\_util\_cap\_free\_um** ([l4\\_cap\\_idx\\_t](#) cap) [L4\\_NOTHROW](#)  
*Return capability index to capability allocator, and unmaps the object.*
- long **l4re\_util\_cap\_last** (void) [L4\\_NOTHROW](#)  
*Return last capability index the allocator can return.*

### 13.9.12.1 Detailed Description

Capability allocator C interface.

### 13.9.12.2 Function Documentation

#### 13.9.12.2.1 l4re\_util\_cap\_last()

```
long l4re_util_cap_last (
    void )
```

Return last capability index the allocator can return.

#### Returns

last/biggest capability index the allocator can return

References [L4\\_END\\_DECLS](#), and [L4\\_NOTHROW](#).

### 13.9.13 Kumem allocator utility

Kumem allocator utility C interface.

Collaboration diagram for Kumem allocator utility:



Kumem allocator utility C interface.

### 13.9.14 Video API

Collaboration diagram for Video API:



#### Data Structures

- struct [l4re\\_video\\_color\\_component\\_t](#)  
*Color component structure.*
- struct [l4re\\_video\\_pixel\\_info\\_t](#)  
*Pixel\_info structure.*
- struct [l4re\\_video\\_goos\\_info\\_t](#)  
*Goos information structure.*
- struct [l4re\\_video\\_view\\_info\\_t](#)  
*View information structure.*
- struct [l4re\\_video\\_view\\_t](#)  
*C representation of a goos view.*

#### Typedefs

- typedef struct [l4re\\_video\\_color\\_component\\_t](#) [l4re\\_video\\_color\\_component\\_t](#)  
*Color component structure.*
- typedef struct [l4re\\_video\\_pixel\\_info\\_t](#) [l4re\\_video\\_pixel\\_info\\_t](#)  
*Pixel\_info structure.*
- typedef [l4\\_cap\\_idx\\_t](#) [l4re\\_video\\_goos\\_t](#)  
*Goos object type.*
- typedef struct [l4re\\_video\\_view\\_info\\_t](#) [l4re\\_video\\_view\\_info\\_t](#)  
*View information structure.*
- typedef struct [l4re\\_video\\_view\\_t](#) [l4re\\_video\\_view\\_t](#)  
*C representation of a goos view.*

#### Enumerations

- enum [l4re\\_video\\_goos\\_info\\_flags\\_t](#) { [F\\_l4re\\_video\\_goos\\_auto\\_refresh](#) = 0x01 , [F\\_l4re\\_video\\_goos\\_pointer](#) = 0x02 , [F\\_l4re\\_video\\_goos\\_dynamic\\_views](#) = 0x04 , [F\\_l4re\\_video\\_goos\\_dynamic\\_buffers](#) = 0x08 }  
*Flags of information on the goos.*
- enum [l4re\\_video\\_view\\_info\\_flags\\_t](#) { [F\\_l4re\\_video\\_view\\_none](#) = 0x00 , [F\\_l4re\\_video\\_view\\_set\\_buffer](#) = 0x01 , [F\\_l4re\\_video\\_view\\_set\\_buffer\\_offset](#) = 0x02 , [F\\_l4re\\_video\\_view\\_set\\_bytes\\_per\\_line](#) = 0x04 , [F\\_l4re\\_video\\_view\\_set\\_pixel](#) = 0x08 , [F\\_l4re\\_video\\_view\\_set\\_position](#) = 0x10 , [F\\_l4re\\_video\\_view\\_dyn\\_allocated](#) = 0x20 , [F\\_l4re\\_video\\_view\\_set\\_background](#) = 0x40 , [F\\_l4re\\_video\\_view\\_set\\_flags](#) = 0x80 , [F\\_l4re\\_video\\_view\\_fully\\_dynamic](#) , [F\\_l4re\\_video\\_view\\_above](#) = 0x01000 , [F\\_l4re\\_video\\_view\\_flags\\_mask](#) = 0xff000 }  
*Flags of information on a view.*

## Functions

- `L4_BEGIN_DECLS` `int l4re_video_goos_info (l4re_video_goos_t goos, l4re_video_goos_info_t *ginfo)`  
`L4_NOTHROW`  
*Get information on a goos.*
- `int l4re_video_goos_refresh (l4re_video_goos_t goos, int x, int y, int w, int h)` `L4_NOTHROW`  
*Flush a rectangle of pixels of the goos screen.*
- `int l4re_video_goos_create_buffer (l4re_video_goos_t goos, unsigned long size, l4_cap_idx_t buffer)`  
`L4_NOTHROW`  
*Create a new buffer (memory buffer) for pixel data.*
- `int l4re_video_goos_delete_buffer (l4re_video_goos_t goos, unsigned idx)` `L4_NOTHROW`  
*Delete a pixel buffer.*
- `int l4re_video_goos_get_static_buffer (l4re_video_goos_t goos, unsigned idx, l4_cap_idx_t buffer)`  
`L4_NOTHROW`  
*Get the data-space capability of the static pixel buffer.*
- `int l4re_video_goos_create_view (l4re_video_goos_t goos, l4re_video_view_t *view)` `L4_NOTHROW`  
*Create a new view (.*
- `int l4re_video_goos_delete_view (l4re_video_goos_t goos, l4re_video_view_t *view)` `L4_NOTHROW`  
*Delete a view.*
- `int l4re_video_goos_get_view (l4re_video_goos_t goos, unsigned idx, l4re_video_view_t *view)`  
`L4_NOTHROW`  
*Get a view for the given index.*
- `L4_BEGIN_DECLS` `int l4re_video_view_refresh (l4re_video_view_t *view, int x, int y, int w, int h)`  
`L4_NOTHROW`  
*Flush the given rectangle of pixels of the given view.*
- `int l4re_video_view_get_info (l4re_video_view_t *view, l4re_video_view_info_t *info)` `L4_NOTHROW`  
*Retrieve information about the given view.*
- `int l4re_video_view_set_info (l4re_video_view_t *view, l4re_video_view_info_t *info)` `L4_NOTHROW`  
*Set properties of the view.*
- `int l4re_video_view_set_viewport (l4re_video_view_t *view, int x, int y, int w, int h, unsigned long bofs)`  
`L4_NOTHROW`  
*Set the viewport parameters of a view.*
- `int l4re_video_view_stack (l4re_video_view_t *view, l4re_video_view_t *pivot, int behind)` `L4_NOTHROW`  
*Change the stacking order in the stack of visible views.*

### 13.9.14.1 Detailed Description

### 13.9.14.2 Typedef Documentation

#### 13.9.14.2.1 l4re\_video\_view\_t

```
typedef struct l4re_video_view_t l4re_video_view_t
```

C representation of a goos view.

A view is a visible rectangle that provides a view to the contents of a buffer (frame buffer) memory object and is placed on a real screen.



### 13.9.14.3 Enumeration Type Documentation

#### 13.9.14.3.1 l4re\_video\_goos\_info\_flags\_t

```
enum l4re_video_goos_info_flags_t
```

Flags of information on the goos.

##### Enumerator

F_l4re_video_goos_auto_refresh	The graphics display is automatically refreshed.
F_l4re_video_goos_pointer	We have a mouse pointer.
F_l4re_video_goos_dynamic_views	Supports dynamically allocated views.
F_l4re_video_goos_dynamic_buffers	Supports dynamically allocated buffers.

Definition at line 29 of file [goos.h](#).

#### 13.9.14.3.2 l4re\_video\_view\_info\_flags\_t

```
enum l4re_video_view_info_flags_t
```

Flags of information on a view.

##### Enumerator

F_l4re_video_view_none	everything for this view is static (the VESA-FB case)
F_l4re_video_view_set_buffer	buffer object for this view can be changed
F_l4re_video_view_set_buffer_offset	buffer offset can be set
F_l4re_video_view_set_bytes_per_line	bytes per line can be set
F_l4re_video_view_set_pixel	pixel type can be set
F_l4re_video_view_set_position	position on screen can be set
F_l4re_video_view_dyn_allocated	View is dynamically allocated.
F_l4re_video_view_set_background	Set view as background for session.
F_l4re_video_view_set_flags	Set view property flags.
F_l4re_video_view_above	Flag the view as stay on top.
F_l4re_video_view_flags_mask	Mask containing all possible property flags.

Definition at line 23 of file [view.h](#).

### 13.9.14.4 Function Documentation

#### 13.9.14.4.1 l4re\_video\_goos\_create\_buffer()

```
int l4re_video_goos_create_buffer (
    l4re_video_goos_t goos,
```

```

    unsigned long size,
    l4_cap_idx_t buffer)

```

Create a new buffer (memory buffer) for pixel data.

#### Parameters

<i>goos</i>	the target object for the operation.
<i>size</i>	the size in bytes for the pixel buffer.
<i>buffer</i>	a capability index to receive the data-space capability for the buffer.

#### Returns

$\geq 0$ : The index of the created buffer (used to assign views and for deletion).  $< 0$ : on error

References [L4\\_CV](#), and [L4\\_NOTHROW](#).

#### 13.9.14.4.2 l4re\_video\_goos\_create\_view()

```

int l4re_video_goos_create_view (
    l4re_video_goos_t goos,
    l4re_video_view_t * view)

```

Create a new view (.).

#### See also

[l4re\\_video\\_view\\_t](#)

#### Parameters

	<i>goos</i>	the goos session to use.
out	<i>view</i>	structure initialized to the new view.

References [L4\\_CV](#), and [L4\\_NOTHROW](#).

#### 13.9.14.4.3 l4re\_video\_goos\_delete\_buffer()

```

int l4re_video_goos_delete_buffer (
    l4re_video_goos_t goos,
    unsigned idx)

```

Delete a pixel buffer.

#### Parameters

<i>goos</i>	the target goos object.
-------------	-------------------------

<i>idx</i>	the buffer index of the buffer to delete (the return value of <a href="#">l4re_video_goos_create_buffer()</a> )
------------	---

References [L4\\_CV](#), and [L4\\_NOTHROW](#).

#### 13.9.14.4.4 l4re\_video\_goos\_delete\_view()

```
int l4re_video_goos_delete_view (  
    l4re_video_goos_t goos,  
    l4re_video_view_t * view)
```

Delete a view.

##### Parameters

<i>goos</i>	the goos session to use.
<i>view</i>	the view to delete, the given data-structure is invalid afterwards.

References [L4\\_CV](#), and [L4\\_NOTHROW](#).

#### 13.9.14.4.5 l4re\_video\_goos\_get\_static\_buffer()

```
int l4re_video_goos_get_static_buffer (  
    l4re_video_goos_t goos,  
    unsigned idx,  
    l4_cap_idx_t buffer)
```

Get the data-space capability of the static pixel buffer.

##### Parameters

<i>goos</i>	The target goos object.
<i>idx</i>	Index of the static buffer.
<i>buffer</i>	A capability index to receive the data-space capability.

This function allows access to static, preexisting pixel buffers. Such static buffers exist for static configurations, such as the VESA framebuffer.

References [L4\\_CV](#), and [L4\\_NOTHROW](#).

#### 13.9.14.4.6 l4re\_video\_goos\_get\_view()

```
int l4re_video_goos_get_view (  
    l4re_video_goos_t goos,  
    unsigned idx,  
    l4re_video_view_t * view)
```

Get a view for the given index.

##### Parameters

	<i>goos</i>	the target goos session.
	<i>idx</i>	the index of the view to retrieve.
out	<i>view</i>	structure initialized to the view with the given index.

This function allows to access static views as provided by the VESA framebuffer (the monitor). However, it also allows to access dynamic views created with [l4re\\_video\\_goos\\_create\\_view\(\)](#).

References [L4\\_END\\_DECLS](#), and [L4\\_NOTHROW](#).

#### 13.9.14.4.7 l4re\_video\_goos\_info()

```
L4_BEGIN_DECLS int l4re_video_goos_info (  
    l4re_video_goos_t goos,  
    l4re_video_goos_info_t * ginfo)
```

Get information on a goos.

##### Parameters

	<i>goos</i>	Goos object
out	<i>ginfo</i>	Pointer to goos information structure.

##### Returns

0 for success, <0 on error

- [-L4\\_ENODEV](#)
- IPC errors

References [L4\\_CV](#), and [L4\\_NOTHROW](#).

**13.9.14.4.8 l4re\_video\_goos\_refresh()**

```
int l4re_video_goos_refresh (
    l4re_video_goos_t goos,
    int x,
    int y,
    int w,
    int h)
```

Flush a rectangle of pixels of the goos screen.

**Parameters**

<i>goos</i>	the target object of the operation.
<i>x</i>	the x-coordinate of the upper left corner of the rectangle
<i>y</i>	the y-coordinate of the upper left corner of the rectangle
<i>w</i>	the width of the rectangle to be flushed
<i>h</i>	the height of the rectangle

References [L4\\_CV](#), and [L4\\_NOTHROW](#).

**13.9.14.4.9 l4re\_video\_view\_get\_info()**

```
int l4re_video_view_get_info (
    l4re_video_view_t * view,
    l4re_video_view_info_t * info)
```

Retrieve information about the given *view*.

**Parameters**

	<i>view</i>	the target view for the operation.
out	<i>info</i>	a buffer receiving the information about the view.

References [L4\\_CV](#), and [L4\\_NOTHROW](#).

**13.9.14.4.10 l4re\_video\_view\_refresh()**

```
L4_BEGIN_DECLS int l4re_video_view_refresh (
    l4re_video_view_t * view,
    int x,
    int y,
    int w,
    int h)
```

Flush the given rectangle of pixels of the given *view*.

**Parameters**

<i>view</i>	the target view of the operation.
<i>x</i>	x-coordinate of the upper left corner
<i>y</i>	y-coordinate of the upper left corner
<i>w</i>	the width of the rectangle
<i>h</i>	the height of the rectangle

References [L4\\_CV](#), and [L4\\_NOTHROW](#).

**13.9.14.4.11 l4re\_video\_view\_set\_info()**

```
int l4re_video_view_set_info (
    l4re_video_view_t * view,
    l4re_video_view_info_t * info)
```

Set properties of the view.

**Parameters**

<i>view</i>	the target view of the operation.
<i>info</i>	the parameters to be set on the view.

Which parameters can be manipulated on a given view can be figured out with [l4re\\_video\\_view\\_get\\_info\(\)](#) and this depends on the concrete instance the view object.

References [L4\\_CV](#), and [L4\\_NOTHROW](#).

**13.9.14.4.12 l4re\_video\_view\_set\_viewport()**

```
int l4re_video_view_set_viewport (
    l4re_video_view_t * view,
    int x,
    int y,
    int w,
    int h,
    unsigned long bofs)
```

Set the viewport parameters of a view.

**Parameters**

<i>view</i>	the target view of the operation.
<i>x</i>	the x-coordinate of the upper left corner on the screen.
<i>y</i>	the y-coordinate of the upper left corner on the screen.
<i>w</i>	the width of the view.

<i>h</i>	the height of the view.
<i>bofs</i>	the offset (in bytes) of the upper left pixel in the memory buffer

This function is a convenience wrapper for [l4re\\_video\\_view\\_set\\_info\(\)](#), just setting the often changed parameters of a dynamic view. With this function a view can be placed on the real screen and at the same time on its backing buffer.

References [L4\\_CV](#), and [L4\\_NOTHROW](#).

#### 13.9.14.4.13 l4re\_video\_view\_stack()

```
int l4re_video_view_stack (
    l4re_video_view_t * view,
    l4re_video_view_t * pivot,
    int behind)
```

Change the stacking order in the stack of visible views.

##### Parameters

<i>view</i>	the target view for the operation.
<i>pivot</i>	the neighbor view, relative to which <i>view</i> shall be stacked. a NULL value allows top ( <i>behind</i> = 1) and bottom ( <i>behind</i> = 0) placement of the view.
<i>behind</i>	describes the placement of the view relative to the <i>pivot</i> view.

References [L4\\_END\\_DECLS](#), and [L4\\_NOTHROW](#).

### 13.9.15 Initial Environment

C interface of the initial environment that is provided to an [L4](#) task.

Collaboration diagram for Initial Environment:



##### Data Structures

- struct [l4re\\_env\\_cap\\_entry\\_t](#)

Entry in the [L4Re](#) environment array for the named initial objects.

## Typedefs

- typedef struct l4re\_env\_cap\_entry\_t **l4re\_env\_cap\_entry\_t**  
Entry in the [L4Re](#) environment array for the named initial objects.

## Functions

- [l4re\\_env\\_t](#) \* [l4re\\_env](#) (void) [L4\\_NOTHROW](#)  
Get [L4Re](#) initial environment.
- [l4\\_kernel\\_info\\_t](#) const \* [l4re\\_kip](#) (void) [L4\\_NOTHROW](#)  
Get Kernel Info Page.
- [l4\\_cap\\_idx\\_t](#) [l4re\\_env\\_get\\_cap](#) (char const \*name) [L4\\_NOTHROW](#)  
Get the capability selector for the object named name.
- [l4\\_cap\\_idx\\_t](#) [l4re\\_env\\_get\\_cap\\_e](#) (char const \*name, [l4re\\_env\\_t](#) const \*e) [L4\\_NOTHROW](#)  
Get the capability selector for the object named name.
- [l4re\\_env\\_cap\\_entry\\_t](#) const \* [l4re\\_env\\_get\\_cap\\_l](#) (char const \*name, unsigned l, [l4re\\_env\\_t](#) const \*e) [L4\\_NOTHROW](#)  
Get the full [l4re\\_env\\_cap\\_entry\\_t](#) for the object named name.

### 13.9.15.1 Detailed Description

C interface of the initial environment that is provided to an [L4](#) task.

#### Include File

```
#include <l4/re/env.h>
```

For an explanation of the default task capabilities see [l4\\_default\\_caps\\_t](#).

For the C++ interface refer to [L4Re::Env](#).

### 13.9.15.2 Function Documentation

#### 13.9.15.2.1 [l4re\\_env\(\)](#)

```
l4re\_env\_t * l4re\_env (  
    void ) [inline]
```

Get [L4Re](#) initial environment.



**Returns**

Pointer to [L4Re](#) initial environment.

**Examples**


[examples/sys/aliens/main.c](#), [examples/sys/isr/main.c](#), [examples/sys/singlestep/main.c](#), [examples/sys/start-with-exc/main.c](#), and [examples/sys/utcb-ipc/main.c](#).

Definition at line 181 of file [env.h](#).

References [L4\\_NOTHROW](#).

Referenced by [l4re\\_env\\_get\\_cap\(\)](#).

Here is the caller graph for this function:

**13.9.15.2.2 l4re\_env\_get\_cap()**

```
l4_cap_idx_t l4re_env_get_cap (
    char const * name) [inline]
```

Get the capability selector for the object named *name*.

**Parameters**

<i>name</i>	is the name of the object to lookup in the initial objects.
-------------	---


**Returns**

A valid capability selector if the object exists or an invalid capability selector if not ([l4\\_is\\_invalid\\_cap\(\)](#)).

Definition at line 220 of file [env.h](#).

References [L4\\_NOTHROW](#), [l4re\\_env\(\)](#), and [l4re\\_env\\_get\\_cap\\_e\(\)](#).

Here is the call graph for this function:



### 13.9.15.2.3 l4re\_env\_get\_cap\_e()

```
l4_cap_idx_t l4re_env_get_cap_e (
    char const * name,
    l4re_env_t const * e) [inline]
```

Get the capability selector for the object named *name*.

#### Parameters

<i>name</i>	is the name of the object to lookup in the initial objects.
<i>e</i>	is the environment structure to use for the operation.

#### Returns

A valid capability selector if the object exists or an invalid capability selector if not ([l4\\_is\\_invalid\\_cap\(\)](#)).

Definition at line 207 of file [env.h](#).

References [l4re\\_env\\_cap\\_entry\\_t::cap](#), [L4\\_INVALID\\_CAP](#), [L4\\_NOTHROW](#), and [l4re\\_env\\_get\\_cap\\_l\(\)](#).

Referenced by [l4re\\_env\\_get\\_cap\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



#### 13.9.15.2.4 l4re\_env\_get\_cap\_l()

```
l4re_env_cap_entry_t const * l4re_env_get_cap_l (
    char const * name,
    unsigned l,
    l4re_env_t const * e) [inline]
```

Get the full [l4re\\_env\\_cap\\_entry\\_t](#) for the object named *name*.

##### Parameters

<i>name</i>	is the name of the object to lookup in the initial objects.
<i>l</i>	is the length of the name string, thus <i>name</i> might not be zero terminated.
<i>e</i>	is the environment structure to use for the operation.

##### Returns


A pointer to an [l4re\\_env\\_cap\\_entry\\_t](#) if the object exists or NULL if not.

Definition at line 189 of file [env.h](#).

References [l4re\\_env\\_cap\\_entry\\_t::flags](#), [L4\\_NOTHROW](#), and [l4re\\_env\\_cap\\_entry\\_t::name](#).

Referenced by [L4Re::Env::get\(\)](#), and [l4re\\_env\\_get\\_cap\\_e\(\)](#).

Here is the caller graph for this function:



#### 13.9.15.2.5 l4re\_kip()

```
l4_kernel_info_t const * l4re_kip (
    void ) [inline]
```

Get Kernel Info Page.

**Returns**

Pointer to Kernel Info Page (KIP) structure.

**Examples**

[examples/libs/shmc/prodcons.c](#), and [examples/sys/aliens/main.c](#).

Definition at line 185 of file [env.h](#).


References [l4\\_kip\(\)](#), and [L4\\_NOTHROW](#).

Referenced by [L4::Poll\\_timeout\\_kipclock::set\(\)](#), and [L4::Poll\\_timeout\\_kipclock::test\(\)](#).

Here is the call graph for this function:




Here is the caller graph for this function:



## 13.10 L4Re C++ Interface

Documentation of the [L4](#) Runtime Environment C++ API.

Collaboration diagram for L4Re C++ Interface:



## Topics

- L4Re Util C++ Interface . . . . . [576](#)  
*Documentation of the [L4 Runtime Environment](#) utility functionality in C++.*
- Console API . . . . . [581](#)

•	<a href="#">Console interface.</a>	
•	Debugging API . . . . .	581
	<i>Debugging Interface.</i>	
•	L4Re ELF Auxiliary Information . . . . .	582
	<i>API for embedding auxiliary information into binary programs.</i>	
•	Event API . . . . .	584
	<a href="#">Event API.</a>	
•	Auxiliary data . . . . .	585
•	Logging interface . . . . .	586
	<i>Interface for log output.</i>	
•	Name-space API . . . . .	586
	<i>API for name spaces that store capabilities.</i>	
•	Parent API . . . . .	587
	<a href="#">Parent interface.</a>	
•	L4Re Protocol identifiers . . . . .	588
	<i>Fix <a href="#">L4Re</a> Protocol Constants.</i>	
•	Region map API . . . . .	589
	<i>Virtual address-space management.</i>	
•	Video API . . . . .	590
	<i>API for framebuffer based graphics.</i>	
•	C++ Exceptions . . . . .	591
•	Vbus API . . . . .	592
	<i>C++ interface of the Vbus API.</i>	


### 13.10.1 Detailed Description

Documentation of the [L4](#) Runtime Environment C++ API.

### 13.10.2 L4Re Util C++ Interface

Documentation of the [L4](#) Runtime Environment utility functionality in C++.

Collaboration diagram for L4Re Util C++ Interface:



## Topics

- L4Re Capability API . . . . . 577
- Kmem•utilities . . . . . 579

## Data Structures


- class [L4Re::Smart\\_cap\\_auto< Unmap\\_flags >](#)  
*Helper for [Unique\\_cap](#) and [Unique\\_del\\_cap](#).*
- class [L4Re::Util::Cap\\_alloc\\_base](#)  
*Capability allocator.*
- class [L4Re::Util::Br\\_manager](#)  
*Buffer-register (BR) manager for [L4::Server](#).*
- class [L4Re::Util::Counting\\_cap\\_alloc< COUNTERTYPE, Dbg >](#)  
*Internal reference-counting cap allocator.*
- class [L4Re::Util::Event\\_buffer\\_t< PAYLOAD >](#)  
*Event\_buffer utility class.*
- class [L4Re::Util::Event\\_buffer\\_consumer\\_t< PAYLOAD >](#)  
*An event buffer consumer.*
- class [L4Re::Util::Vcon\\_svr< SVR >](#)  
*[Console](#) server template class.*
- class [L4Re::Util::Video::Goos\\_svr](#)  
*Goos server class.*

### 13.10.2.1 Detailed Description

Documentation of the [L4](#) Runtime Environment utility functionality in C++.

### 13.10.2.2 L4Re Capability API

Collaboration diagram for L4Re Capability API:



## Data Structures

- class [L4Re::Cap\\_alloc](#)  
*Capability allocator interface.*
- class [L4Re::Smart\\_cap\\_auto< Unmap\\_flags >](#)  
*Helper for [Unique\\_cap](#) and [Unique\\_del\\_cap](#).*
- class [L4Re::Smart\\_count\\_cap< Unmap\\_flags >](#)  
*Helper for [Ref\\_cap](#) and [Ref\\_del\\_cap](#).*
- class [L4Re::Util::Smart\\_cap\\_auto< Unmap\\_flags >](#)  
*Helper for [Unique\\_cap](#) and [Unique\\_del\\_cap](#).*
- class [L4Re::Util::Smart\\_count\\_cap< Unmap\\_flags >](#)  
*Helper for [Ref\\_cap](#) and [Ref\\_del\\_cap](#).*
- struct [L4Re::Util::Ref\\_cap< T >](#)  
*Automatic capability that implements automatic free and unmap of the capability selector.*
- struct [L4Re::Util::Ref\\_del\\_cap< T >](#)  
*Automatic capability that implements automatic free and unmap+delete of the capability selector.*

## Functions

- `template<typename T>`  
`Ref\_cap< T >::Cap L4Re::Util::make\_ref\_cap ()`  
*Allocate a capability slot and wrap it in a [Ref\\_cap](#).*
- `template<typename T>`  
`Ref\_del\_cap< T >::Cap L4Re::Util::make\_ref\_del\_cap ()`  
*Allocate a capability slot and wrap it in a [Ref\\_del\\_cap](#).*

## Variables

- `\_Cap\_alloc L4Re::Util::cap\_alloc`  
*Capability allocator.*

### 13.10.2.2.1 Detailed Description

### 13.10.2.2.2 Function Documentation

#### 13.10.2.2.2.1 `make_ref_cap()`

```
template<typename T>
Ref\_cap< T >::Cap L4Re::Util::make\_ref\_cap ()
```

Allocate a capability slot and wrap it in a [Ref\\_cap](#).

#### Template Parameters

<code>T</code>	Type of capability the slot is used for.
----------------	--

Definition at line 195 of file [cap\\_alloc](#).

References [cap\\_alloc](#).



#### 13.10.2.2.2.2 make\_ref\_del\_cap()

```
template<typename T>
Ref_del_cap< T >::Cap L4Re::Util::make_ref_del_cap ()
```

Allocate a capability slot and wrap it in a [Ref\\_del\\_cap](#).

##### Template Parameters

<i>T</i>	Type of capability the slot is used for.
----------	--

Definition at line 204 of file [cap\\_alloc](#).

References [cap\\_alloc](#).

#### 13.10.2.2.3 Variable Documentation

##### 13.10.2.2.3.1 cap\_alloc

```
_Cap_alloc L4Re::Util::cap_alloc [extern]
```

Capability allocator.

This is the instance of the capability allocator that is used by usual applications.

The capability allocator uses the [Counting\\_cap\\_alloc](#), a reference-counting thread-safe capability allocator, that keeps a reference counter for each managed capability selector.


##### Examples

[examples/libs/l4re/c++/mem\\_alloc/ma+rm.cc](#), [examples/libs/l4re/c++/shared\\_ds/ds\\_clnt.cc](#), [examples/libs/l4re/c++/shared\\_ds/ds\\_d](#) and [examples/libs/l4re/streammap/client.cc](#).

Referenced by [L4Re::Util::Br\\_manager::alloc\\_buffer\\_demand\(\)](#), [L4Re::Util::Smart\\_count\\_cap< Unmap\\_flags >::copy\(\)](#), [L4Re::Util::Smart\\_cap\\_auto< Unmap\\_flags >::free\(\)](#), [L4Re::Util::Smart\\_count\\_cap< Unmap\\_flags >::free\(\)](#), [L4Re::Util::Event\\_t< Default\\_event\\_payload >::init\(\)](#), [L4Re::Util::Event\\_t< Default\\_event\\_payload >::init\\_poll\(\)](#), [make\\_ref\\_cap\(\)](#), [make\\_ref\\_del\\_cap\(\)](#), [make\\_shared\\_cap\(\)](#), [make\\_shared\\_del\\_cap\(\)](#), [make\\_unique\\_cap\(\)](#), [make\\_unique\\_del\\_cap\(\)](#), [L4Re::Util::Br\\_manager::realloc\\_rcv\\_cap\(\)](#), and [L4Re::Util::Object\\_registry::unregister\\_obj\(\)](#).

#### 13.10.2.3 Kumem utilities

Collaboration diagram for Kumem utilities:



## Functions

- `int L4Re::Util::kumem_alloc (l4_addr_t *mem, unsigned pages_order, L4::Cap< L4::Task > task=L4Re::Env::env() ->task(), L4::Cap< L4Re::Rm > rm=L4Re::Env::env() ->rm()) noexcept`  
*Allocate state area.*

### 13.10.2.3.1 Detailed Description

### 13.10.2.3.2 Function Documentation

#### 13.10.2.3.2.1 kumem\_alloc()

```
int L4Re::Util::kumem_alloc (
    l4_addr_t * mem,
    unsigned pages_order,
    L4::Cap< L4::Task > task = L4Re::Env::env() ->task(),
    L4::Cap< L4Re::Rm > rm = L4Re::Env::env() ->rm())    [noexcept]
```

Allocate state area.

#### Parameters

out	<i>mem</i>	Pointer to memory that has been allocated.
	<i>pages_order</i>	Size to allocate, in log2 pages.
	<i>task</i>	Task to use for allocation.
	<i>rm</i>	Region manager to use for allocation.

#### Return values

0	for success
<0	error code on failure

#### Note

The amount of kernel-user memory that can be allocated at once is limited by the used kernel implementation. The minimum allocatable amount is one page. A portable implementation should not depend on allocations greater than 16KiB to succeed.

References [L4Re::Env::env\(\)](#).


Here is the call graph for this function:



### 13.10.3 Console API

[Console](#) interface.

Collaboration diagram for Console API:



#### Data Structures

- class [L4Re::Console](#)  
*Console class.*

#### 13.10.3.1 Detailed Description

[Console](#) interface.

### 13.10.4 Debugging API

Debugging Interface.

Collaboration diagram for Debugging API:



#### Data Structures

- class [L4Re::Debug\\_obj](#)  
*Debug interface.*

### 13.10.4.1 Detailed Description

Debugging Interface.

The debugging interface can be provided to retrieve, or log debugging information for an object. Each class may realize the debug interface to provide debugging functionality. For example, the region map objects provide a facility to dump the currently established memory regions.


See also

L4::Debug\_obj for more information.

### 13.10.5 L4Re ELF Auxiliary Information

API for embedding auxiliary information into binary programs.

Collaboration diagram for L4Re ELF Auxiliary Information:



#### Data Structures

- struct [l4re\\_elf\\_aux\\_t](#)  
*Generic header for each auxiliary vector element.*
- struct [l4re\\_elf\\_aux\\_vma\\_t](#)  
*Auxiliary vector element for a reserved virtual memory area.*
- struct [l4re\\_elf\\_aux\\_mword\\_t](#)  
*Auxiliary vector element for a single unsigned data word.*

#### Macros

- #define [L4RE\\_ELF\\_AUX\\_ELEM](#) const \_\_attribute\_\_((used, section(".ro.l4re\_elf\_aux"), aligned(sizeof(l4\_umword\_t))))  
*Define an auxiliary vector element.*
- #define [L4RE\\_ELF\\_AUX\\_ELEM\\_T](#)(type, id, tag, val...)  
*Define an auxiliary vector element.*

#### Typedefs

- typedef struct l4re\_elf\_aux\_t **l4re\_elf\_aux\_t**  
*Generic header for each auxiliary vector element.*
- typedef struct l4re\_elf\_aux\_vma\_t **l4re\_elf\_aux\_vma\_t**  
*Auxiliary vector element for a reserved virtual memory area.*
- typedef struct l4re\_elf\_aux\_mword\_t **l4re\_elf\_aux\_mword\_t**  
*Auxiliary vector element for a single unsigned data word.*

## Enumerations

- enum {  
[L4RE\\_ELF\\_AUX\\_T\\_NONE](#) = 0 , [L4RE\\_ELF\\_AUX\\_T\\_VMA](#) , [L4RE\\_ELF\\_AUX\\_T\\_STACK\\_SIZE](#) ,  
[L4RE\\_ELF\\_AUX\\_T\\_STACK\\_ADDR](#) ,  
[L4RE\\_ELF\\_AUX\\_T\\_KIP\\_ADDR](#) , [L4RE\\_ELF\\_AUX\\_T\\_EX\\_REGS\\_FLAGS](#) }

### 13.10.5.1 Detailed Description

API for embedding auxiliary information into binary programs.

This API allows information for the binary loader to be embedded into a binary application. This information can be reserved areas in the virtual memory of an application and things such as the stack size to be allocated for the first application thread.

### 13.10.5.2 Macro Definition Documentation

#### 13.10.5.2.1 L4RE\_ELF\_AUX\_ELEM

```
#define L4RE_ELF_AUX_ELEM const __attribute__((used, section(".ro14re_elf_aux"), aligned(sizeof(l4\_umword\_t))))
```

Define an auxiliary vector element.

This is the generic method for defining auxiliary vector elements. A more convenient way is to use [L4RE\\_ELF\\_AUX\\_ELEM\\_T](#).

Usage:

```
L4RE\_ELF\_AUX\_ELEM l4re\_elf\_aux\_vma\_t decl_name =  
{ L4RE\_ELF\_AUX\_T\_VMA, sizeof(l4re\_elf\_aux\_vma\_t), 0x2000, 0x4000 };
```

Definition at line 41 of file [elf\\_aux.h](#).

#### 13.10.5.2.2 L4RE\_ELF\_AUX\_ELEM\_T

```
#define L4RE_ELF_AUX_ELEM_T(  
    type,  
    id,  
    tag,  
    val...)
```

Value:

```
static L4RE\_ELF\_AUX\_ELEM type id = {tag, sizeof(type), val}
```

Define an auxiliary vector element.

#### Parameters

<i>type</i>	is the data type for the element (e.g., <a href="#">l4re_elf_aux_vma_t</a> )
<i>id</i>	is the identifier (variable name) for the declaration (the variable is defined with <code>static</code> storage class)
<i>tag</i>	is the tag value for the element e.g., <a href="#">L4RE_ELF_AUX_T_VMA</a>

<i>val</i>	are the values to be set in the descriptor
------------	--

Usage:

```
L4RE_ELF_AUX_ELEM_T(l4re_elf_aux_vma_t, decl_name, L4RE_ELF_AUX_T_VMA, 0x2000, 0x4000 );
```

Definition at line 56 of file [elf\\_aux.h](#).

### 13.10.5.3 Enumeration Type Documentation

#### 13.10.5.3.1 anonymous enum

anonymous enum

##### Enumerator

L4RE_ELF_AUX_T_NONE	Tag for an invalid element in the auxiliary vector.
L4RE_ELF_AUX_T_VMA	Tag for descriptor for a reserved virtual memory area.
L4RE_ELF_AUX_T_STACK_SIZE	Tag for descriptor that defines the stack size for the first application thread.
L4RE_ELF_AUX_T_STACK_ADDR	Tag for descriptor that defines the stack address for the first application thread.
L4RE_ELF_AUX_T_KIP_ADDR	Tag for descriptor that defines the KIP address for the binaries address space.
L4RE_ELF_AUX_T_EX_REGS_FLAGS	Tag for descriptor to override ex_regs() flags.

Definition at line 59 of file [elf\\_aux.h](#).

### 13.10.6 Event API

[Event API](#).

Collaboration diagram for Event API:



#### Data Structures

- class [L4Re::Event](#)  
*Event class.*
- struct [L4Re::Default\\_event\\_payload](#)  
*Default event stream payload.*
- class [L4Re::Event\\_buffer\\_t< PAYLOAD >](#)  
*Event buffer class.*

### 13.10.6.1 Detailed Description

Event API.

On top of a shared [L4Re::Dataspace](#) (and optionally using [L4::Triggerable](#)), the event API implements asynchronous event transmission from an event provider (server) to an event receiver (client). Events are put into an [Event\\_buffer\\_t](#) residing on the shared [L4Re::Dataspace](#).

This interface is usually not used directly. Instead use [L4Re::Util::Event\\_t](#) for clients. An example server portion is implemented in [L4Re::Util::Event\\_svr](#).

This interface is usually used with [L4Re::Default\\_event\\_payload](#) which delivers HID events modeled on the Linux evdev API, and the interface's methods allow further querying of information about the HID event streams.

### 13.10.7 Auxiliary data

Collaboration diagram for Auxiliary data:



#### Data Structures

- struct [l4re\\_aux\\_t](#)  
*Auxiliary descriptor.*

#### Typedefs

- typedef struct l4re\_aux\_t [l4re\\_aux\\_t](#)  
*Auxiliary descriptor.*

#### Enumerations


- enum [l4re\\_aux\\_ldr\\_flags\\_t](#)  
*Flags for program loading.*

### 13.10.7.1 Detailed Description

## 13.10.8 Logging interface

Interface for log output.

Collaboration diagram for Logging interface:



### Data Structures

- class [L4Re::Log](#)  
*Log interface class.*

### 13.10.8.1 Detailed Description

Interface for log output.

The logging interface provides a facility sending log output. One purpose of the interface is to serialize the output and provide the possibility to tag output sent to a specific log object.

## 13.10.9 Name-space API

API for name spaces that store capabilities.

Collaboration diagram for Name-space API:



### Data Structures

- class [L4Re::Namespace](#)  
*Name-space interface.*



### 13.10.9.1 Detailed Description

API for name spaces that store capabilities.


This is a basic abstraction for managing a mapping from human-readable names to capabilities. In particular, a name can also be mapped to a capability that refers to another name space object. By this means name spaces can be constructed hierarchically.

Name spaces play a central role in [L4Re](#), because the implementation of the name space objects determines the policy which capabilities (which objects) are accessible to a client of a name space.

### 13.10.10 Parent API

[Parent](#) interface.

Collaboration diagram for Parent API:



#### Data Structures

- class [L4Re::Parent](#)  
*[Parent](#) interface.*

### 13.10.10.1 Detailed Description

[Parent](#) interface.

The parent interface provides means for an [L4](#) task to signal changes in its execution state. The main purpose is to signal program termination to the program that started it, so that its resources can be reclaimed. In a typical [L4Re](#) system, this program will be Moe or Ned.

See also

[L4Re::Parent](#) for information about the concrete interface.

### 13.10.11 L4Re Protocol identifiers

Fix [L4Re](#) Protocol Constants.

Collaboration diagram for L4Re Protocol identifiers:



#### Enumerations

- enum [L4Re::Dataspace\\_::Opcodes](#)  
*Data-space communication-protocol opcodes.*
- enum [L4Re::Event\\_::Opcodes](#)  
*Event communication-protocol opcodes.*
- enum [L4Re::Inhibitor\\_::Opcodes](#)  
*Inhibitor communication-protocol opcodes.*
- enum [L4Re::Log\\_::Opcodes](#)  
*Logging-service communication-protocol opcodes.*
- enum [L4Re::Mem\\_alloc\\_::Opcodes](#)  
*Memory-allocator communication-protocol opcodes.*
- enum [L4Re::Namespace\\_::Opcodes](#)  
*Name-space communication-protocol opcodes.*
- enum [L4Re::Parent\\_::Opcodes](#)  
*Parent communication-protocol opcodes.*
- enum [L4re\\_protocols](#) {  
[L4RE\\_PROTO\\_DATASPACE](#) = 0x4000 , [L4RE\\_PROTO\\_NAMESPACE](#) , [L4RE\\_PROTO\\_PARENT](#) ,  
[L4RE\\_PROTO\\_GOOS](#) ,  
[L4RE\\_PROTO\\_RSVD\\_1](#) , [L4RE\\_PROTO\\_RM](#) , [L4RE\\_PROTO\\_EVENT](#) , [L4RE\\_PROTO\\_INHIBITOR](#) ,  
[L4RE\\_PROTO\\_DMA\\_SPACE](#) , [L4RE\\_PROTO\\_MMIO\\_SPACE](#) , [L4RE\\_PROTO\\_ITAS](#) , [L4RE\\_PROTO\\_MEM\\_ALLOC](#)  
, [L4RE\\_PROTO\\_REMOTE\\_ACCESS](#) , [L4RE\\_PROTO\\_DEBUG](#) = ~0x7fffL }  
*Common [L4Re](#) Protocol Constants.*
- enum [L4Re::Rm\\_::Opcodes](#)  
*Region-map communication-protocol opcodes.*
- enum [L4Re::Video::Goos\\_::Opcodes](#)  
*Frame buffer communication-protocol opcodes.*

#### 13.10.11.1 Detailed Description

Fix [L4Re](#) Protocol Constants.

### 13.10.11.2 Enumeration Type Documentation

#### 13.10.11.2.1 L4re\_protocols

enum [L4re\\_protocols](#)

Common [L4Re](#) Protocol Constants.

##### Enumerator

L4RE_PROTO_DATASPACE	ID for <a href="#">L4Re::Dataspace</a> RPCs.
L4RE_PROTO_NAMESPACE	ID for <a href="#">L4Re::Namespace</a> RPCs.
L4RE_PROTO_PARENT	ID for <a href="#">L4Re::Parent</a> RPCs.
L4RE_PROTO_GOOS	ID for <a href="#">L4Re::Video::Goos</a> RPCs.
L4RE_PROTO_RSVD_1	Reserved ID.
L4RE_PROTO_RM	ID for <a href="#">L4Re::Rm</a> RPCs.
L4RE_PROTO_EVENT	ID for <a href="#">L4Re::Event</a> RPCs.
L4RE_PROTO_INHIBITOR	ID for <a href="#">L4Re::Inhibitor</a> RPCs.
L4RE_PROTO_DMA_SPACE	ID for <a href="#">L4Re::Dma_space</a> RPCs.
L4RE_PROTO_MMIO_SPACE	ID for <a href="#">L4Re::Mmio_space</a> .
L4RE_PROTO_ITAS	ID for <a href="#">L4Re::Itas</a> .
L4RE_PROTO_MEM_ALLOC	ID for <a href="#">L4Re::Mem_alloc</a> .
L4RE_PROTO_REMOTE_ACCESS	ID for <a href="#">L4Re::Remote_access</a> .
L4RE_PROTO_DEBUG	ID for debugging RPCs.

Definition at line 24 of file [protocols.h](#).

### 13.10.12 Region map API

Virtual address-space management.

Collaboration diagram for Region map API:



#### Data Structures

- class [L4Re::Rm](#)  
*Region map.*

### 13.10.12.1 Detailed Description

Virtual address-space management.

A region map object implements two protocols. The first protocol is the kernel page-fault protocol, to resolve page faults for threads running in an [L4](#) task. The second protocol is the region map protocol itself, which allows managing the virtual memory address space of an [L4](#) task.

There are two basic concepts provided by the region map abstraction:

- **Areas** are reserved ranges in the virtual memory address space.
- **Regions** are ranges that are backed by (part of) a dataspace, i.e. accessing them results in access to the physical memory the dataspace manages.

Note that regions may live outside of areas and that an area does not necessarily contain any region.

Areas can be reserved for special use or for attaching a dataspace at a later time. When attaching a dataspace, the user can instruct the region map to search for an appropriate range to attach to. Regions are skipped in this search since they already have dataspace attached to them, and, depending on [L4Re::Rm::F::In\\_area](#), areas are skipped because they are reserved. Amongst others, areas can be used to attach several dataspace inside a certain range of addresses without interference from other threads.

When a region map receives a page fault IPC, the region map will check if the faulting virtual address lies in a region. If yes, it will answer the page fault IPC with a mapping from the backing dataspace. If not, an error is returned.

Depending on the system type, an attached dataspace might or might not be mapped eagerly. MMU-based systems resort to lazy mapping while systems without MMU do eager mappings by default. The [L4Re::Rm::F::Eager\\_map](#) and [L4Re::Rm::F::No\\_eager\\_map](#) flags can be used to force the respective behaviour, independent of the underlying system. In case both flags are given, the [L4Re::Rm::F::No\\_eager\\_map](#) flag wins.

See also

[L4Re::Dataspace](#), [L4Re::Rm](#),  
[Memory management - Data Spaces and the Region Map](#)

### 13.10.13 Video API

API for framebuffer based graphics.

Collaboration diagram for Video API:



## Data Structures

- class [L4Re::Video::Color\\_component](#)  
*A color component.*
- class [L4Re::Video::Pixel\\_info](#)  
*Pixel information.*

### 13.10.13.1 Detailed Description

API for framebuffer based graphics.

Contains the basic APIs that abstract framebuffers and views into them for [L4Re](#) applications.

### 13.10.14 C++ Exceptions

Collaboration diagram for C++ Exceptions:



## Files

- file [exceptions](#)  
*Base exceptions.*

## Data Structures

- class [L4::Exception\\_tracer](#)  
*Back-trace support for exceptions.*
- class [L4::Base\\_exception](#)  
*Base class for all exceptions, thrown by the [L4Re](#) framework.*
- class [L4::Runtime\\_error](#)  
*Exception for an abstract runtime error.*
- class [L4::Out\\_of\\_memory](#)  
*Exception signalling insufficient memory.*
- class [L4::Element\\_already\\_exists](#)  
*Exception for duplicate element insertions.*
- class [L4::Unknown\\_error](#)  
*Exception for an unknown condition.*
- class [L4::Element\\_not\\_found](#)  
*Exception for a failed lookup (element not found).*
- class [L4::Invalid\\_capability](#)  
*Indicates that an invalid object was invoked.*
- class [L4::Com\\_error](#)  
*Error conditions during IPC.*
- class [L4::Bounds\\_error](#)  
*Access out of bounds.*

## Macros


- `#define L4_CXX_EXCEPTION_BACKTRACE 20`  
*Number of instruction pointers in backtrace.*

### 13.10.14.1 Detailed Description

### 13.10.15 Vbus API

C++ interface of the Vbus API.

Collaboration diagram for Vbus API:



## Data Structures

- class [L4vbus::Pm< DEC >](#)  
*Power-management API mixin.*
- class [L4vbus::Device](#)  
*Device on a [L4vbus::Vbus](#).*
- class [L4vbus::Icu](#)  
*Vbus Interrupt controller API.*
- class [L4vbus::Vbus](#)  
*The virtual bus ([Vbus](#)) interface.*
- class [L4vbus::Gpio\\_pin](#)  
*A GPIO pin.*
- class [L4vbus::Gpio\\_module](#)  
*A [Gpio\\_module](#) groups multiple GPIO pins together.*
- class [L4vbus::Pci\\_host\\_bridge](#)  
*A Pci host bridge.*
- class [L4vbus::Pci\\_dev](#)  
*A PCI device.*

### 13.10.15.1 Detailed Description

C++ interface of the Vbus API.

The virtual bus (Vbus) is a hierarchical (tree) structure of device nodes where each device has a set of resources attached to it. Each virtual bus provides an Icu ([Interrupt controller](#)) for interrupt handling.

The Vbus interface allows a client to find and query devices present on his virtual bus. After obtaining a device handle for a specific device the client can enumerate its resources.

Refer to [L4 Vbus functions](#) for the C API.

#### Include File

```
#include <l4/vbus/vbus>
```

#### Include File

```
#include <l4/vbus/vbus_gpio>
```


#### Include File

```
#include <l4/vbus/vbus_pci>
```

## 13.11 L4SHM-based ring buffer implementation

The library provides a non-locking (strictly 1:1) shared-memory-based ring buffer implementation based on the L4SHM library.

Collaboration diagram for L4SHM-based ring buffer implementation:



### Topics

- Sender • . . . . . [594](#)
- Receiver . . . . . [594](#)
- Internal • . . . . . [594](#)

### 13.11.1 Detailed Description


The library provides a non-locking (strictly 1:1) shared-memory-based ring buffer implementation based on the L4SHM library.

It requires an already allocated L4SHM area to be attached to sender and receiver. It will allocate an SHM chunk within this area and provides functions to produce data and consume data in FIFO order from the ring buffer.

The sender side of the buffer needs to be initialized *before* the receiver side, because allocation of the SHM chunk and the necessary signals is done on the sender side and the receiver initialization tries to attach to these objects.


### 13.11.2 Sender

Collaboration diagram for Sender:




### 13.11.3 Receiver

Collaboration diagram for Receiver:



### 13.11.4 Internal

Collaboration diagram for Internal:





## Data Structures

- struct [l4shmc\\_ringbuf\\_head\\_t](#)  
*Head field of a ring buffer.*
- struct [l4shmc\\_ringbuf\\_t](#)  
*Ring buffer.*

## Macros

- #define [L4SHMC\\_RINGBUF\\_HEAD](#)(ringbuf)  
*Get ring buffer head pointer.*
- #define [L4SHMC\\_RINGBUF\\_DATA](#)(ringbuf)  
*Get ring buffer data pointer.*
- #define [L4SHMC\\_RINGBUF\\_DATA\\_SIZE](#)(ringbuf)  
*Get size of data area.*

### 13.11.4.1 Detailed Description

### 13.11.4.2 Macro Definition Documentation

#### 13.11.4.2.1 L4SHMC\_RINGBUF\_DATA

```
#define L4SHMC_RINGBUF_DATA(  
    ringbuf)
```

##### Value:

```
(L4SHMC\_RINGBUF\_HEAD(ringbuf)->data)
```

Get ring buffer data pointer.

##### Parameters

<i>ringbuf</i>	<a href="#">l4shmc_ringbuf_t</a> struct
----------------	---

Definition at line 114 of file [ringbuf.h](#).

#### 13.11.4.2.2 L4SHMC\_RINGBUF\_DATA\_SIZE

```
#define L4SHMC_RINGBUF_DATA_SIZE(  
    ringbuf)
```

##### Value:

```
((ringbuf)->_size - sizeof(l4shmc\_ringbuf\_head\_t))
```

Get size of data area.

**Parameters**

<i>ringbuf</i>	<a href="#">l4shmc_ringbuf_t</a> struct
----------------	---

Definition at line 123 of file [ringbuf.h](#).

**13.11.4.2.3 L4SHMC\_RINGBUF\_HEAD**

```
#define L4SHMC_RINGBUF_HEAD(  
    ringbuf)
```

**Value:**

```
((l4shmc_ringbuf_head_t*) ((ringbuf)->_addr))
```

Get ring buffer head pointer.

**Parameters**


<i>ringbuf</i>	<a href="#">l4shmc_ringbuf_t</a> struct
----------------	---

Definition at line 105 of file [ringbuf.h](#).

**13.12 Shared Memory Library**

L4SHM provides a shared memory infrastructure that establishes a shared memory area between multiple parties and uses a fast notification mechanism.

Collaboration diagram for Shared Memory Library:

**Topics**

- [Chunks](#) . . . . . 602
- [Signals](#) . . . . . 615

## Functions

- [L4\\_BEGIN\\_DECLS](#) long [l4shmc\\_create](#) (char const \*shmc\_name)  
*Create a shared memory area.*
- long [l4shmc\\_attach](#) (char const \*shmc\_name, l4shmc\_area\_t \*shmarea)  
*Attach to a shared memory area.*
- long [l4shmc\\_get\\_client\\_nr](#) (l4shmc\_area\_t const \*shmarea)  
*Determine the client number of the shared memory region.*
- long [l4shmc\\_mark\\_client\\_initialized](#) (l4shmc\_area\_t \*shmarea)  
*Mark this shared memory client as 'initialized'.*
- long [l4shmc\\_get\\_initialized\\_clients](#) (l4shmc\_area\_t \*shmarea, l4\_umword\_t \*bitmask)  
*Fetch the `_clients_init_done` bitmask of the shared memory area.*
- long [l4shmc\\_connect\\_chunk\\_signal](#) (l4shmc\_chunk\_t \*chunk, l4shmc\_signal\_t \*signal)  
*Connect a signal with a chunk.*
- long [l4shmc\\_area\\_size](#) (l4shmc\_area\_t const \*shmarea)  
*Get size of shared memory area.*
- long [l4shmc\\_area\\_size\\_free](#) (l4shmc\_area\_t const \*shmarea)  
*Get free size of shared memory area.*
- long [l4shmc\\_area\\_overhead](#) (void)  
*Get memory overhead per area that is not available for chunks.*
- long [l4shmc\\_chunk\\_overhead](#) (void)  
*Get memory overhead required in addition to the chunk capacity for adding one chunk.*

### 13.12.1 Detailed Description

L4SHM provides a shared memory infrastructure that establishes a shared memory area between multiple parties and uses a fast notification mechanism.

A shared memory area consists of chunks and signals. A chunk is a defined chunk of memory within the memory area with a maximum size. A chunk is filled (written) by a producer and read by a consumer. When a producer has finished writing to the chunk it signals a data ready notification to the consumer.

A consumer attaches to a chunk and waits for the producer to fill the chunk. After reading out the chunk it marks the chunk free again.

A shared memory area can have multiple chunks.

The interface is divided in three roles.

- The master role, responsible for setting up a shared memory area.
- A producer, generating data into a chunk
- A consumer, receiving data.

A signal can be connected with a chunk or can be used independently (e.g. for multiple chunks).

## 13.12.2 Function Documentation

### 13.12.2.1 l4shmc\_area\_overhead()

```
long l4shmc_area_overhead (  
    void )
```

Get memory overhead per area that is not available for chunks.

#### Returns

Size of the overhead in bytes.

References [L4\\_CV](#).

### 13.12.2.2 l4shmc\_area\_size()

```
long l4shmc_area_size (  
    l4shmc_area_t const * shmarea)
```

Get size of shared memory area.

#### Parameters

<i>shmarea</i>	Shared memory area.
----------------	---------------------

#### Return values

$>0$	Size of the shared memory area.
$<0$	Error.

References [L4\\_CV](#).

### 13.12.2.3 l4shmc\_area\_size\_free()

```
long l4shmc_area_size_free (  
    l4shmc_area_t const * shmarea)
```

Get free size of shared memory area.

To get the max size to pass to `l4shmc_add_chunk`, subtract [l4shmc\\_chunk\\_overhead\(\)](#).

#### Parameters

<i>shmarea</i>	Shared memory area.
----------------	---------------------

#### Returns

Size of the shared memory area.

References [L4\\_CV](#).

#### 13.12.2.4 l4shmc\_attach()

```
long l4shmc_attach (
    char const * shmc_name,
    l4shmc_area_t * shmarea)
```

Attach to a shared memory area.

##### Parameters

	<i>shmc_name</i>	Name of the shared memory area.
out	<i>shmarea</i>	Pointer to shared memory area descriptor to be filled with information for the shared memory area.

On success, the data in 'shmarea' contains a client number which can be used to mutual agree about client initialization:

- [l4shmc\\_get\\_client\\_nr\(\)](#) returns the client number stored in 'shmarea'. The first attached client will get 0 and this number is increased for each attached client.
- [l4shmc\\_mark\\_client\\_initialized\(\)](#) tells other clients that this client has finished its initialization.
- [l4shmc\\_get\\_initialized\\_clients\(\)](#) returns the bitmap of initialized clients attached to this shared memory.

##### Return values

0	Success.
<0	Error.

##### Examples

[examples/libs/shmc/prodcons.c](#).

References [L4\\_CV](#).

#### 13.12.2.5 l4shmc\_chunk\_overhead()

```
long l4shmc_chunk_overhead (
    void )
```

Get memory overhead required in addition to the chunk capacity for adding one chunk.

##### Returns

Size of the overhead in bytes.

References [L4\\_END\\_DECLS](#).

### 13.12.2.6 l4shmc\_connect\_chunk\_signal()

```
long l4shmc_connect_chunk_signal (  
    l4shmc_chunk_t * chunk,  
    l4shmc_signal_t * signal)
```

Connect a signal with a chunk.

#### Parameters

<i>chunk</i>	Chunk to attach the signal to.
<i>signal</i>	Signal to attach.

#### Return values

0	Success.
<0	Error.

#### Examples

[examples/libs/shmc/prodcons.c](#).

References [L4\\_CV](#), and [L4\\_INLINE](#).

### 13.12.2.7 l4shmc\_create()

```
L4_BEGIN_DECLS long l4shmc_create (  
    char const * shmc_name)
```

Create a shared memory area.

#### Parameters

<i>shmc_name</i>	Name of the shared memory area.
------------------	---------------------------------

#### Return values

0	Success.
-L4_ENOMEM	The requested size is too big.
-L4_ENOENT	No valid capability with the name of the shared memory area found.
<0	Errors from l4re_rm_attach or l4re_ns_register_obj_srv.

#### Examples

[examples/libs/shmc/prodcons.c](#).

References [L4\\_CV](#).

### 13.12.2.8 l4shmc\_get\_client\_nr()

```
long l4shmc_get_client_nr (
    l4shmc_area_t const * shmarea)
```

Determine the client number of the shared memory region.

#### Parameters

<i>shmarea</i>	The shared memory area.
----------------	-------------------------

#### Returns

client number.

References [L4\\_CV](#).

### 13.12.2.9 l4shmc\_get\_initialized\_clients()

```
long l4shmc_get_initialized_clients (
    l4shmc_area_t * shmarea,
    l4_umword_t * bitmask)
```

Fetch the `_clients_init_done` bitmask of the shared memory area.

#### Parameters

	<i>shmarea</i>	The shared memory area.
out	<i>bitmask</i>	The bitmask describing which clients are initialized.

#### Return values

0	Success.
<0	Error.

#### See also

[l4shmc\\_mark\\_client\\_initialized\(\)](#), [l4shmc\\_get\\_client\\_nr\(\)](#)

#### Examples

[examples/libs/shmc/prodcons.c](#).

References [L4\\_CV](#).

### 13.12.2.10 l4shmc\_mark\_client\_initialized()

```
long l4shmc_mark_client_initialized (
    l4shmc_area_t * shmarea)
```

Mark this shared memory client as 'initialized'.

The corresponding bit is set in the `_clients_init_done` bitmask. The bitmask can be fetched with [l4shmc\\_get\\_initialized\\_clients\(\)](#).

#### Parameters

<i>shmarea</i>	The shared memory area.
----------------	-------------------------

#### Return values

0	Success.
<0	Error.


#### Examples

[examples/libs/shmc/prodcons.c](#).

References [L4\\_CV](#).

## 13.12.3 Chunks

Collaboration diagram for Chunks:



#### Topics

- [Producer](#) ..... 607
- [Consumer](#) ..... 610



## Functions

- long [l4shmc\\_add\\_chunk](#) (l4shmc\_area\_t \*shmarea, char const \*chunk\_name, [l4\\_umword\\_t](#) chunk\_capacity, l4shmc\_chunk\_t \*chunk)  
*Add a chunk in the shared memory area.*
- long [l4shmc\\_get\\_chunk](#) (l4shmc\_area\_t \*shmarea, char const \*chunk\_name, l4shmc\_chunk\_t \*chunk)  
*Get chunk out of shared memory area.*
- long [l4shmc\\_get\\_chunk\\_to](#) (l4shmc\_area\_t \*shmarea, char const \*chunk\_name, [l4\\_umword\\_t](#) timeout\_ms, l4shmc\_chunk\_t \*chunk)  
*Get chunk out of shared memory area, with timeout.*
- long [l4shmc\\_iterate\\_chunk](#) (l4shmc\_area\_t const \*shmarea, char const \*\*chunk\_name, long offs)  
*Iterate over names of all existing chunks.*
- void \* [l4shmc\\_chunk\\_ptr](#) (l4shmc\_chunk\_t const \*chunk)  
*Get data pointer to chunk.*
- long [l4shmc\\_chunk\\_capacity](#) (l4shmc\_chunk\_t const \*chunk)  
*Get capacity of a chunk.*
- l4shmc\_signal\_t \* [l4shmc\\_chunk\\_signal](#) (l4shmc\_chunk\_t const \*chunk)  
*Get the registered signal of a chunk.*

### 13.12.3.1 Detailed Description

### 13.12.3.2 Function Documentation

#### 13.12.3.2.1 l4shmc\_add\_chunk()

```
long l4shmc_add_chunk (
    l4shmc_area_t * shmarea,
    char const * chunk_name,
    l4\_umword\_t chunk_capacity,
    l4shmc_chunk_t * chunk)
```

Add a chunk in the shared memory area.

#### Parameters

	<i>shmarea</i>	The shared memory area to put the chunk in.
	<i>chunk_name</i>	Name of the chunk.
	<i>chunk_capacity</i>	Capacity for payload of the chunk in bytes.
out	<i>chunk</i>	Chunk structure to fill in.

#### Return values

0	Success.
<0	Error.

#### Examples

[examples/libs/shmc/prodcons.c](#).

References [L4\\_CV](#).

#### 13.12.3.2.2 l4shmc\_chunk\_capacity()

```
long l4shmc_chunk_capacity (  
    l4shmc_chunk_t const * chunk)    [inline]
```

Get capacity of a chunk.

##### Parameters

<i>chunk</i>	Chunk.
--------------	--------

##### Returns

Capacity of the chunk in bytes.

References [L4\\_CV](#), and [L4\\_INLINE](#).

#### 13.12.3.2.3 l4shmc\_chunk\_ptr()

```
void * l4shmc_chunk_ptr (  
    l4shmc_chunk_t const * chunk)    [inline]
```

Get data pointer to chunk.

##### Parameters

<i>chunk</i>	Chunk.
--------------	--------

##### Returns

Chunk pointer.

##### Examples

[examples/libs/shmc/prodcons.c](#).

References [L4\\_CV](#), and [L4\\_INLINE](#).

**13.12.3.2.4 l4shmc\_chunk\_signal()**

```
l4shmc_signal_t * l4shmc_chunk_signal (
    l4shmc_chunk_t const * chunk) [inline]
```

Get the registered signal of a chunk.

**Parameters**

<i>chunk</i>	Chunk.
--------------	--------

**Return values**

0	No signal has been registered with this chunk.
!=0	Pointer to signal otherwise.

References [L4\\_CV](#), and [L4\\_INLINE](#).

**13.12.3.2.5 l4shmc\_get\_chunk()**

```
long l4shmc_get_chunk (
    l4shmc_area_t * shmarea,
    char const * chunk_name,
    l4shmc_chunk_t * chunk) [inline]
```

Get chunk out of shared memory area.

**Parameters**

	<i>shmarea</i>	Shared memory area.
	<i>chunk_name</i>	Name of the chunk.
out	<i>chunk</i>	Chunk data structure to fill.

**Return values**

0	Success.
<0	Error.

**Examples**

[examples/libs/shmc/prodcons.c](#).

References [L4\\_CV](#).

### 13.12.3.2.6 l4shmc\_get\_chunk\_to()

```
long l4shmc_get_chunk_to (
    l4shmc_area_t * shmarea,
    char const * chunk_name,
    l4_umword_t timeout_ms,
    l4shmc_chunk_t * chunk)
```

Get chunk out of shared memory area, with timeout.

#### Parameters

	<i>shmarea</i>	Shared memory area.
	<i>chunk_name</i>	Name of the chunk.
	<i>timeout_ms</i>	Timeout in milliseconds to wait for the chunk to appear in the shared memory area.
out	<i>chunk</i>	Chunk data structure to fill.

#### Return values

0	Success.
<0	Error.

References [L4\\_CV](#).

### 13.12.3.2.7 l4shmc\_iterate\_chunk()

```
long l4shmc_iterate_chunk (
    l4shmc_area_t const * shmarea,
    char const ** chunk_name,
    long offs)
```

Iterate over names of all existing chunks.

#### Parameters

<i>shmarea</i>	Shared memory area.
<i>chunk_name</i>	Where the name of the current chunk will be stored
<i>offs</i>	0 to start iteration, return value of previous call to <a href="#">l4shmc_iterate_chunk()</a> to get next chunk

#### Return values

0	No more chunks available.
<0	Error.
>0	Iterator value for the next call.

References [L4\\_CV](#).

### 13.12.3.3 Producer

Collaboration diagram for Producer:



### Functions

- long [l4shmc\\_chunk\\_try\\_to\\_take](#) (l4shmc\_chunk\_t \*chunk)  
*Try to mark chunk busy.*
- long [l4shmc\\_chunk\\_try\\_to\\_take\\_for\\_writing](#) (l4shmc\_chunk\_t \*chunk)  
*Try to mark chunk busy writing.*
- long [l4shmc\\_chunk\\_try\\_to\\_take\\_for\\_overwriting](#) (l4shmc\_chunk\_t \*chunk)  
*Try to mark the chunk busy writing after it was ready for reading.*
- long [l4shmc\\_chunk\\_ready](#) (l4shmc\_chunk\_t \*chunk, [l4\\_umword\\_t](#) size)  
*Mark chunk as filled (ready).*
- long [l4shmc\\_chunk\\_ready\\_sig](#) (l4shmc\_chunk\_t \*chunk, [l4\\_umword\\_t](#) size)  
*Mark chunk as filled (ready) and signal consumer.*
- long [l4shmc\\_is\\_chunk\\_clear](#) (l4shmc\_chunk\_t const \*chunk)  
*Check whether chunk is free.*

#### 13.12.3.3.1 Detailed Description

#### 13.12.3.3.2 Function Documentation

##### 13.12.3.3.2.1 l4shmc\_chunk\_ready()

```

long l4shmc_chunk_ready (
    l4shmc_chunk_t * chunk,
    l4_umword_t size) [inline]
  
```

Mark chunk as filled (ready).

### Parameters

<i>chunk</i>	chunk.
<i>size</i>	Size of data in the chunk, in bytes.

**Return values**

<i>0</i>	Success.
<i>&lt;0</i>	Error.

References [L4\\_CV](#), and [L4\\_INLINE](#).

**13.12.3.3.2.2 l4shmc\_chunk\_ready\_sig()**

```
long l4shmc_chunk_ready_sig (  
    l4shmc_chunk_t * chunk,  
    l4_umword_t size) [inline]
```

Mark chunk as filled (ready) and signal consumer.

**Parameters**

<i>chunk</i>	chunk.
<i>size</i>	Size of data in the chunk, in bytes.

**Return values**

<i>0</i>	Success.
<i>&lt;0</i>	Error.

**Examples**

[examples/libs/shmc/prodcons.c](#).

References [L4\\_CV](#), and [L4\\_INLINE](#).

**13.12.3.3.2.3 l4shmc\_chunk\_try\_to\_take()**

```
long l4shmc_chunk_try_to_take (  
    l4shmc_chunk_t * chunk) [inline]
```

Try to mark chunk busy.

**Parameters**

<i>chunk</i>	chunk to mark.
--------------	----------------

**Return values**

<i>0</i>	Chunk could be taken.
----------	-----------------------

$< 0$	Chunk could not be taken, try again.
-------	--------------------------------------

#### Examples

[examples/libs/shmc/prodcons.c](#).

References [L4\\_CV](#), and [L4\\_INLINE](#).

#### 13.12.3.3.2.4 l4shmc\_chunk\_try\_to\_take\_for\_overwriting()

```
long l4shmc_chunk_try_to_take_for_overwriting (
    l4shmc_chunk_t * chunk) [inline]
```

Try to mark the chunk busy writing after it was ready for reading.

#### Parameters

<i>chunk</i>	chunk to mark busy writing.
--------------	-----------------------------

This function is used by the producer to overwrite a message if the consumer did not read the message within an expected time. This function can only be used if the consumer uses [l4shmc\\_chunk\\_try\\_to\\_take\\_for\\_reading\(\)](#) before reading the chunk.

#### Return values

$0$	Chunk could be taken and can be written.
$< 0$	Chunk could not be taken, try again.

References [L4\\_CV](#), and [L4\\_INLINE](#).

#### 13.12.3.3.2.5 l4shmc\_chunk\_try\_to\_take\_for\_writing()

```
long l4shmc_chunk_try_to_take_for_writing (
    l4shmc_chunk_t * chunk) [inline]
```

Try to mark chunk busy writing.

This function is actually an alias for [l4shmc\\_chunk\\_try\\_to\\_take\(\)](#).

#### Parameters

<i>chunk</i>	chunk to mark busy writing.
--------------	-----------------------------

#### Return values

---

<code>0</code>	Chunk could be taken and can be written.
<code>&lt;0</code>	Chunk could not be taken, try again.

References [L4\\_CV](#), and [L4\\_INLINE](#).

#### 13.12.3.3.2.6 `l4shmc_is_chunk_clear()`

```
long l4shmc_is_chunk_clear (
    l4shmc_chunk_t const * chunk) [inline]
```

Check whether chunk is free.

##### Parameters

<code>chunk</code>	Chunk to check.
--------------------	-----------------

##### Return values

<code>!=0</code>	Chunk is clear.
<code>0</code>	Chunk is not clear.

References [L4\\_CV](#), and [L4\\_INLINE](#).

#### 13.12.3.4 Consumer

Collaboration diagram for Consumer:



##### Functions

- long [l4shmc\\_chunk\\_try\\_to\\_take\\_for\\_reading](#) (l4shmc\_chunk\_t \*chunk)  
*Try to mark chunk busy reading.*
- long [l4shmc\\_enable\\_chunk](#) (l4shmc\_chunk\_t \*chunk)  
*Enable a signal connected with a chunk.*
- long [l4shmc\\_wait\\_chunk](#) (l4shmc\_chunk\_t \*chunk)  
*Wait on a specific chunk.*
- long [l4shmc\\_wait\\_chunk\\_to](#) (l4shmc\_chunk\_t \*chunk, [l4\\_timeout\\_t](#) timeout)



*Check whether a specific chunk has an event pending, with timeout.*

- long [l4shmc\\_wait\\_chunk\\_try](#) (l4shmc\_chunk\_t \*chunk)

*Check whether a specific chunk has an event pending.*

- long [l4shmc\\_chunk\\_consumed](#) (l4shmc\_chunk\_t \*chunk)

*Mark a chunk as free.*

- long [l4shmc\\_is\\_chunk\\_ready](#) (l4shmc\_chunk\_t const \*chunk)

*Check whether data is available.*

- long [l4shmc\\_chunk\\_size](#) (l4shmc\_chunk\_t const \*chunk)

*Get current size of a chunk.*

#### 13.12.3.4.1 Detailed Description

#### 13.12.3.4.2 Function Documentation

##### 13.12.3.4.2.1 l4shmc\_chunk\_consumed()

```
long l4shmc_chunk_consumed (
    l4shmc_chunk_t * chunk) [inline]
```

Mark a chunk as free.

#### Parameters

<i>chunk</i>	Chunk to mark as free.
--------------	------------------------

#### Return values

0	Success.
<0	Error.

#### Examples

[examples/libs/shmc/prodcons.c](#).

References [L4\\_CV](#).

##### 13.12.3.4.2.2 l4shmc\_chunk\_size()

```
long l4shmc_chunk_size (
    l4shmc_chunk_t const * chunk) [inline]
```

Get current size of a chunk.

#### Parameters

<i>chunk</i>	Chunk.
--------------	--------

#### Returns

Current size of the chunk in bytes.

#### Examples

[examples/libs/shmc/prodcons.c](#).

References [L4\\_CV](#), and [L4\\_INLINE](#).

#### 13.12.3.4.2.3 l4shmc\_chunk\_try\_to\_take\_for\_reading()

```
long l4shmc_chunk_try_to_take_for_reading (  
    l4shmc_chunk_t * chunk) [inline]
```

Try to mark chunk busy reading.

##### Parameters

<i>chunk</i>	chunk to mark busy reading.
--------------	-----------------------------

##### Return values

0	Chunk could be taken and can be read.
<0	Chunk could not be taken, try again.

References [L4\\_CV](#), and [L4\\_INLINE](#).

#### 13.12.3.4.2.4 l4shmc\_enable\_chunk()

```
long l4shmc_enable_chunk (  
    l4shmc_chunk_t * chunk)
```

Enable a signal connected with a chunk.

##### Parameters

<i>chunk</i>	Chunk to enable.
--------------	------------------

##### Return values

0	Success.
<0	Error.

A signal must be enabled before waiting when the consumer waits on any signal. Enabling is not needed if the consumer waits for a specific signal or chunk.

References [L4\\_CV](#), and [L4\\_INLINE](#).

#### 13.12.3.4.2.5 l4shmc\_is\_chunk\_ready()

```
long l4shmc_is_chunk_ready (
    l4shmc_chunk_t const * chunk) [inline]
```

Check whether data is available.

##### Parameters

<i>chunk</i>	Chunk to check.
--------------	-----------------

##### Return values

<i>!=0</i>	Data is available.
<i>0</i>	No data available.

References [L4\\_CV](#), and [L4\\_INLINE](#).

#### 13.12.3.4.2.6 l4shmc\_wait\_chunk()

```
long l4shmc_wait_chunk (
    l4shmc_chunk_t * chunk) [inline]
```

Wait on a specific chunk.

##### Parameters

<i>chunk</i>	Chunk to wait for.
--------------	--------------------

##### Return values

<i>0</i>	Success.
<i>&lt;0</i>	Error.

##### Examples

[examples/libs/shmc/prodcons.c](#).

References [L4\\_CV](#).

#### 13.12.3.4.2.7 l4shmc\_wait\_chunk\_to()

```
long l4shmc_wait_chunk_to (
    l4shmc_chunk_t * chunk,
    l4_timeout_t timeout)
```

Check whether a specific chunk has an event pending, with timeout.

##### Parameters

<i>chunk</i>	Chunk to check.
<i>timeout</i>	Timeout.

##### Return values

0	Success.
<0	Error.

The return code indicates whether an event was pending or not. Success means an event was pending, if an receive timeout error is returned no event was pending.

References [L4\\_CV](#), and [L4\\_INLINE](#).

#### 13.12.3.4.2.8 l4shmc\_wait\_chunk\_try()

```
long l4shmc_wait_chunk_try (
    l4shmc_chunk_t * chunk) [inline]
```

Check whether a specific chunk has an event pending.

##### Parameters

<i>chunk</i>	Chunk to check.
--------------	-----------------

##### Return values


0	Success.
<0	Error.

The return code indicates whether an event was pending or not. Success means an event was pending, if an receive timeout error is returned no event was pending.

References [L4\\_CV](#), and [L4\\_INLINE](#).

### 13.12.4 Signals

Collaboration diagram for Signals:



#### Topics

- [Producer](#) . . . . . 618
- [Consumer](#) . . . . . 619

#### Functions

- [long l4shmc\\_add\\_signal](#) (l4shmc\_area\_t \*shmarea, char const \*signal\_name, l4shmc\_signal\_t \*signal)  
Add a signal for the shared memory area.
- [long l4shmc\\_attach\\_signal](#) (l4shmc\_area\_t \*shmarea, char const \*signal\_name, [l4\\_cap\\_idx\\_t](#) thread, l4shmc\_signal\_t \*signal)  
Attach to signal.
- [long l4shmc\\_get\\_signal](#) (l4shmc\_area\_t \*shmarea, char const \*signal\_name, l4shmc\_signal\_t \*signal)  
Get signal object from the shared memory area.
- [l4\\_cap\\_idx\\_t l4shmc\\_signal\\_cap](#) (l4shmc\_signal\_t const \*signal)  
Get the signal capability of a signal.
- [long l4shmc\\_check\\_magic](#) (l4shmc\_chunk\_t const \*chunk)  
Check magic value of a chunk.

#### 13.12.4.1 Detailed Description

#### 13.12.4.2 Function Documentation

##### 13.12.4.2.1 l4shmc\_add\_signal()

```

long l4shmc_add_signal (
    l4shmc_area_t * shmarea,
    char const * signal_name,
    l4shmc_signal_t * signal)

```

Add a signal for the shared memory area.

**Parameters**

	<i>shmarea</i>	The shared memory area.
	<i>signal_name</i>	Name of the signal.
out	<i>signal</i>	Signal structure to fill in.

**Return values**

0	Success.
<0	Error.

**Examples**

[examples/libs/shmc/prodcons.c](#).

References [L4\\_CV](#), and [L4\\_INLINE](#).

**13.12.4.2.2 l4shmc\_attach\_signal()**

```
long l4shmc_attach_signal (
    l4shmc_area_t * shmarea,
    char const * signal_name,
    l4_cap_idx_t thread,
    l4shmc_signal_t * signal)
```

Attach to signal.

**Parameters**

	<i>shmarea</i>	Shared memory area.
	<i>signal_name</i>	Name of the signal.
	<i>thread</i>	Thread capability index to attach the signal to.
out	<i>signal</i>	Signal data structure to fill.

**Return values**

0	Success.
<0	Error.

**Examples**

[examples/libs/shmc/prodcons.c](#).

References [L4\\_CV](#).

#### 13.12.4.2.3 l4shmc\_check\_magic()

```
long l4shmc_check_magic (
    l4shmc_chunk_t const * chunk) [inline]
```

Check magic value of a chunk.

##### Parameters

<i>chunk</i>	Chunk.
--------------	--------

##### Return values

0	Magic value is not valid.
>0	Chunk is OK, the magic value is valid.

References [L4\\_CV](#).

#### 13.12.4.2.4 l4shmc\_get\_signal()

```
long l4shmc_get_signal (
    l4shmc_area_t * shmarea,
    char const * signal_name,
    l4shmc_signal_t * signal)
```

Get signal object from the shared memory area.

##### Parameters

	<i>shmarea</i>	Shared memory area.
	<i>signal_name</i>	Name of the signal.
out	<i>signal</i>	Signal data structure to fill.

##### Return values

0	Success.
<0	Error.

References [L4\\_CV](#).

#### 13.12.4.2.5 l4shmc\_signal\_cap()

```
l4\_cap\_idx\_t l4shmc_signal_cap (
    l4shmc_signal_t const * signal) [inline]
```

Get the signal capability of a signal.

**Parameters**

<i>signal</i>	Signal.
---------------	---------

**Returns**

Capability of the signal object.

References [L4\\_CV](#), and [L4\\_INLINE](#).

**13.12.4.3 Producer**

Collaboration diagram for Producer:

**Functions**

- long [l4shmc\\_trigger](#) (l4shmc\_signal\_t \*signal)  
*Trigger a signal.*

**13.12.4.3.1 Detailed Description****13.12.4.3.2 Function Documentation****13.12.4.3.2.1 l4shmc\_trigger()**

```

long l4shmc_trigger (
    l4shmc_signal_t * signal) [inline]
  
```

Trigger a signal.

**Parameters**

<i>signal</i>	Signal to trigger.
---------------	--------------------



**Return values**

0	Success.
<0	Error.

**Examples**

[examples/libs/shmc/prodcons.c](#).

References [L4\\_CV](#), and [L4\\_INLINE](#).

**13.12.4.4 Consumer**

Collaboration diagram for Consumer:

**Functions**

- long [l4shmc\\_enable\\_signal](#) (l4shmc\_signal\_t \*signal)  
*Enable a signal.*
- long [l4shmc\\_wait\\_any](#) (l4shmc\_signal\_t \*\*retsignal)  
*Wait on any signal.*
- long [l4shmc\\_wait\\_any\\_try](#) (l4shmc\_signal\_t \*\*retsignal)  
*Check whether any waited signal has an event pending.*
- long [l4shmc\\_wait\\_any\\_to](#) (l4\_timeout\_t timeout, l4shmc\_signal\_t \*\*retsignal)  
*Wait for any signal with timeout.*
- long [l4shmc\\_wait\\_signal](#) (l4shmc\_signal\_t \*signal)  
*Wait on a specific signal.*
- long [l4shmc\\_wait\\_signal\\_to](#) (l4shmc\_signal\_t \*signal, l4\_timeout\_t timeout)  
*Wait on a specific signal, with timeout.*
- long [l4shmc\\_wait\\_signal\\_try](#) (l4shmc\_signal\_t \*signal)  
*Check whether a specific signal has an event pending.*

#### 13.12.4.4.1 Detailed Description

#### 13.12.4.4.2 Function Documentation

##### 13.12.4.4.2.1 l4shmc\_enable\_signal()

```
long l4shmc_enable_signal (  
    l4shmc_signal_t * signal)
```

Enable a signal.

#### Parameters

<i>signal</i>	Signal to enable.
---------------	-------------------

#### Return values

0	Success.
<0	Error.

A signal must be enabled before waiting when the consumer waits on any signal. Enabling is not needed if the consumer waits for a specific signal or chunk.

References [L4\\_CV](#).

##### 13.12.4.4.2.2 l4shmc\_wait\_any()

```
long l4shmc_wait_any (  
    l4shmc_signal_t ** retsignal) [inline]
```

Wait on any signal.

#### Parameters

out	<i>retsignal</i>	Signal received.
-----	------------------	------------------

#### Return values

0	Success.
<0	Error.

References [L4\\_CV](#), and [L4\\_INLINE](#).

#### 13.12.4.4.2.3 l4shmc\_wait\_any\_to()

```
long l4shmc_wait_any_to (
    l4_timeout_t timeout,
    l4shmc_signal_t ** retsignal)
```

Wait for any signal with timeout.

##### Parameters

	<i>timeout</i>	Timeout.
out	<i>retsignal</i>	Signal that has the event pending if any.

##### Return values

0	Success.
<0	Error.

The return code indicates whether an event was pending or not. Success means an event was pending, if an receive timeout error is returned no event was pending.

References [L4\\_CV](#), and [L4\\_INLINE](#).

#### 13.12.4.4.2.4 l4shmc\_wait\_any\_try()

```
long l4shmc_wait_any_try (
    l4shmc_signal_t ** retsignal) [inline]
```

Check whether any waited signal has an event pending.

##### Parameters

out	<i>retsignal</i>	Signal that has the event pending if any.
-----	------------------	---

##### Return values

0	Success.
<0	Error.

The return code indicates whether an event was pending or not. Success means an event was pending, if an receive timeout error is returned no event was pending.

References [L4\\_CV](#).

#### 13.12.4.4.2.5 l4shmc\_wait\_signal()

```
long l4shmc_wait_signal (  
    l4shmc_signal_t * signal)    [inline]
```

Wait on a specific signal.

##### Parameters

<i>signal</i>	Signal to wait for.
---------------	---------------------

##### Return values

0	Success.
<0	Error.

##### Examples

[examples/libs/shmc/prodcons.c](#).

References [L4\\_CV](#).

#### 13.12.4.4.2.6 l4shmc\_wait\_signal\_to()

```
long l4shmc_wait_signal_to (  
    l4shmc_signal_t * signal,  
    l4_timeout_t timeout)
```

Wait on a specific signal, with timeout.

##### Parameters

<i>signal</i>	Signal to wait for.
<i>timeout</i>	Timeout.

##### Return values

0	Success.
<0	Error.

References [L4\\_CV](#), and [L4\\_INLINE](#).

#### 13.12.4.4.2.7 l4shmc\_wait\_signal\_try()

```
long l4shmc_wait_signal_try (
    l4shmc_signal_t * signal) [inline]
```

Check whether a specific signal has an event pending.

##### Parameters

<i>signal</i>	Signal to check.
---------------	------------------

##### Return values

0	Success.
<0	Error.

The return code indicates whether an event was pending or not. Success means an event was pending, if an receive timeout error is returned no event was pending.

References [L4\\_CV](#), and [L4\\_INLINE](#).

## 13.13 Sigma0 API

Sigma0 API bindings.

Collaboration diagram for Sigma0 API:



### Topics

- [Internal constants](#) . . . . . 628  
*Internal sigma0 definitions.*

### Files

- file [sigma0.h](#)  
*Sigma0 interface.*

## Enumerations

- enum `l4sigma0_return_flags_t` {  
`L4SIGMA0_OK` , `L4SIGMA0_NOTALIGNED` , `L4SIGMA0_IPCERROR` , `L4SIGMA0_NOFPAGE` ,  
`L4SIGMA0_4` , `L4SIGMA0_5` , `L4SIGMA0_SMALLERFPAGE` }

*Return flags of libsigma0 functions.*

## Functions

- `L4_BEGIN_DECLS l4_kernel_info_t * l4sigma0_map_kip (l4_cap_idx_t sigma0, void *addr, unsigned log2↵_size)`  
*Map the kernel info page from sigma0 to addr.*
- int `l4sigma0_map_mem (l4_cap_idx_t sigma0, l4_addr_t phys, l4_addr_t virt, l4_addr_t size)`  
*Request a memory mapping from sigma0.*
- int `l4sigma0_map_iomem (l4_cap_idx_t sigma0, l4_addr_t phys, l4_addr_t virt, l4_addr_t size, int cached)`  
*Request IO memory from sigma0.*
- int `l4sigma0_map_anypage (l4_cap_idx_t sigma0, l4_addr_t map_area, unsigned log2_map_size, l4_addr_t *base, unsigned sz)`  
*Request an arbitrary free page of RAM.*
- void `l4sigma0_debug_dump (l4_cap_idx_t sigma0)`  
*Request sigma0 to dump internal debug information.*
- char const \* `l4sigma0_map_errstr (int err)`  
*Get user readable error messages for the return codes.*

### 13.13.1 Detailed Description

Sigma0 API bindings.

Convenience bindings for the Sigma0 protocol.

### 13.13.2 Enumeration Type Documentation

#### 13.13.2.1 l4sigma0\_return\_flags\_t

enum `l4sigma0_return_flags_t`

Return flags of libsigma0 functions.

#### Enumerator

<code>L4SIGMA0_OK</code>	Ok.
<code>L4SIGMA0_NOTALIGNED</code>	Phys, virt or size not aligned.
<code>L4SIGMA0_IPCERROR</code>	IPC error.
<code>L4SIGMA0_NOFPAGE</code>	No fpage received.
<code>L4SIGMA0_SMALLERFPAGE</code>	Superpage requested but smaller flexpage received.

Definition at line 76 of file [sigma0.h](#).

### 13.13.3 Function Documentation

#### 13.13.3.1 `l4sigma0_debug_dump()`

```
void l4sigma0_debug_dump (
    l4_cap_idx_t sigma0)
```

Request sigma0 to dump internal debug information.

##### Parameters

<i>sigma0</i>	Capability selector for the sigma0 gate.
---------------	--

The debug information, such as internal memory maps, as well as statistics about the internal allocators is dumped to the kernel debugger.

References [L4\\_CV](#), and [L4\\_INLINE](#).

#### 13.13.3.2 `l4sigma0_map_anypage()`

```
int l4sigma0_map_anypage (
    l4_cap_idx_t sigma0,
    l4_addr_t map_area,
    unsigned log2_map_size,
    l4_addr_t * base,
    unsigned sz)
```

Request an arbitrary free page of RAM.

##### Parameters

	<i>sigma0</i>	Capability selector for the sigma0 gate.
	<i>map_area</i>	The base address of the local virtual memory area where the page should be mapped.
	<i>log2_map_size</i>	The size of the requested page log 2 (the size in bytes is $2^{\text{log2\_map\_size}}$ ). This must be at least the minimal page size. By specifying larger sizes the largest possible hardware page size will be used.
out	<i>base</i>	Physical address of the page received (i.e. the send base of the received mapping if any).
	<i>sz</i>	Size to map by the server in $2^{\text{sz}}$ bytes.

##### Return values

<i>0</i>	Success.
<i>-L4SIGMA0_IPCERROR</i>	IPC error.
<i>-L4SIGMA0_NOFPAGE</i>	No fpage received.

This function requests arbitrary free memory from sigma0. It should be used whenever spare memory is needed, instead of requesting specific physical memory with [l4sigma0\\_map\\_mem\(\)](#).

See [l4sigma0\\_map\\_errstr\(\)](#) to get a description of the return value.

References [L4\\_CV](#).

### 13.13.3.3 l4sigma0\_map\_errstr()

```
char const * l4sigma0_map_errstr (
    int err) [inline]
```

Get user readable error messages for the return codes.

#### Parameters

<i>err</i>	The error code reported by the <i>map</i> functions.
------------	--

#### Returns

A string containing the error message.

Definition at line 210 of file [sigma0.h](#).

References [L4\\_INLINE](#).

### 13.13.3.4 l4sigma0\_map\_iomem()

```
int l4sigma0_map_iomem (
    l4_cap_idx_t sigma0,
    l4_addr_t phys,
    l4_addr_t virt,
    l4_addr_t size,
    int cached)
```

Request IO memory from sigma0.

#### Parameters

<i>sigma0</i>	Capability selector for the sigma0 gate.
<i>phys</i>	The physical address to be requested (page aligned).
<i>virt</i>	The virtual address where the memory should be mapped to (page aligned).
<i>size</i>	The size of the IO memory area to be mapped (multiple of page size)
<i>cached</i>	Requests cacheable IO memory if 1 and uncached if 0.

#### Return values

0	Success.
-L4SIGMA0_NOTALIGNED	<i>phys</i> , <i>virt</i> , or <i>size</i> are not aligned.
-L4SIGMA0_IPCERROR	IPC error.
-L4SIGMA0_NOFPAGE	No fpage received.

This function is similar to [l4sigma0\\_map\\_mem\(\)](#), the difference is that it requests IO memory. IO memory is everything that is not known to be normal RAM. Also ACPI tables or the BIOS memory is treated as IO memory.

See [l4sigma0\\_map\\_errstr\(\)](#) to get a description of the return value.

References [L4\\_CV](#).



### 13.13.3.5 l4sigma0\_map\_kip()

```
L4_BEGIN_DECLS l4_kernel_info_t * l4sigma0_map_kip (
    l4_cap_idx_t sigma0,
    void * addr,
    unsigned log2_size)
```

Map the kernel info page from sigma0 to addr.

#### Parameters

<i>sigma0</i>	Capability selector for the sigma0 gate.
<i>addr</i>	Start of the receive window to receive KIP in.
<i>log2_size</i>	Size of the receive window to receive KIP in.

#### Returns

Address KIP was mapped to, 0 indicates an error.

### 13.13.3.6 l4sigma0\_map\_mem()

```
int l4sigma0_map_mem (
    l4_cap_idx_t sigma0,
    l4_addr_t phys,
    l4_addr_t virt,
    l4_addr_t size)
```

Request a memory mapping from sigma0.

#### Parameters

<i>sigma0</i>	Capability selector for the sigma0 gate.
<i>phys</i>	The physical address of the requested page (must be at least aligned to the minimum page size).
<i>virt</i>	The virtual address where the paged should be mapped in the local address space (must be at least aligned to the minimum page size).
<i>size</i>	The size of the requested page, this must be a multiple of the minimum page size.

#### Return values

0	Success.
-L4SIGMA0_NOTALIGNED	phys, virt, or size are not aligned.
-L4SIGMA0_IPCERROR	IPC error.
-L4SIGMA0_NOFPAGE	No fpage received.

This function only maps normal RAM. To map other memory, use [l4sigma0\\_map\\_iomem\(\)](#). See also there for the distinction between both memory types.

This is the direct method to request memory from sigma0. There is also the indirect method where sigma0 will answer page faults with a mapping that is one-to-one between the faulting virtual page and the backing physical page. See [L4::Pager::page\\_fault\(\)](#). For an overview of the memory hierarchy, see [Memory management - Data Spaces and the Region Map](#).

See [l4sigma0\\_map\\_errstr\(\)](#) to get a description of the return value.

References [L4\\_CV](#).

### 13.13.4 Internal constants

Internal sigma0 definitions.

Collaboration diagram for Internal constants:



#### Macros

- **#define SIGMA0\_REQ\_MAGIC** ~0xFFUL  
*Request magic.*
- **#define SIGMA0\_REQ\_MASK** ~0xFFUL  
*Request mask.*
- **#define SIGMA0\_REQ\_ID\_MASK** 0xF0  
*ID mask.*
- **#define SIGMA0\_REQ\_ID\_FPAGE\_RAM** 0x60  
*RAM.*
- **#define SIGMA0\_REQ\_ID\_FPAGE\_IOMEM** 0x70  
*I/O memory.*
- **#define SIGMA0\_REQ\_ID\_FPAGE\_IOMEM\_CACHED** 0x80  
*Cached I/O memory.*
- **#define SIGMA0\_REQ\_ID\_FPAGE\_ANY** 0x90  
*Any.*
- **#define SIGMA0\_REQ\_ID\_KIP** 0xA0  
*KIP.*
- **#define SIGMA0\_REQ\_ID\_DEBUG\_DUMP** 0xC0  
*Debug dump.*
- **#define SIGMA0\_REQ\_ID\_COV** 0xE0  
*Trigger cov dump.*
- **#define SIGMA0\_IS\_MAGIC\_REQ**(d1)  
*Check if magic.*
- **#define SIGMA0\_REQ**(x)  
*Construct.*

- `#define SIGMA0_REQ_FPAGE_RAM (SIGMA0_REQ(FPAGE_RAM))`  
*RAM.*
- `#define SIGMA0_REQ_FPAGE_IOMEM (SIGMA0_REQ(FPAGE_IOMEM))`  
*I/O memory.*
- `#define SIGMA0_REQ_FPAGE_IOMEM_CACHED (SIGMA0_REQ(FPAGE_IOMEM_CACHED))`  
*Cache I/O memory.*
- `#define SIGMA0_REQ_FPAGE_ANY (SIGMA0_REQ(FPAGE_ANY))`  
*Any.*
- `#define SIGMA0_REQ_KIP (SIGMA0_REQ(KIP))`  
*KIP.*
- `#define SIGMA0_REQ_DEBUG_DUMP (SIGMA0_REQ(DEBUG_DUMP))`  
*Debug dump.*
- `#define SIGMA0_REQ_COV (SIGMA0_REQ(COV))`  
*Cov.*

#### 13.13.4.1 Detailed Description

Internal sigma0 definitions.

## 13.14 Small C++ Template Library

### Namespaces

- namespace `cxx`  
*Our C++ library.*

### Data Structures

- class `L4::Alloc_list`  
*A simple list-based allocator.*
- class `cxx::List_item`  
*Basic list item.*
- struct `cxx::Pair< First, Second >`  
*Pair of two values.*
- class `cxx::Base_slab< Obj_size, Slab_size, Max_free, Alloc >`  
*Basic slab allocator.*
- class `cxx::Slab< Type, Slab_size, Max_free, Alloc >`  
*Slab allocator for object of type `Type`.*
- class `cxx::Base_slab_static< Obj_size, Slab_size, Max_free, Alloc >`  
*Merged slab allocator (allocators for objects of the same size are merged together).*
- class `cxx::Slab_static< Type, Slab_size, Max_free, Alloc >`  
*Merged slab allocator (allocators for objects of the same size are merged together).*
- class `cxx::Nothrow`  
*Helper type to distinguish the `operator new` version that does not throw exceptions.*
- class `cxx::New_allocator< _Type >`  
*Standard allocator based on `operator new ()`.*
- class `L4::String`  
*A null-terminated string container class.*

## Functions

- `template<typename A, typename ... ARGS>`  
`constexpr A const & cxx::min (A const &a1, A const &a2, ARGS const &...a)`  
*Get the minimum of  $a_1$  and  $a_2$  up to  $a_N$ .*
- `template<typename A, typename ... ARGS>`  
`constexpr A const & cxx::min (cxx::identity_t< A > const &a1, cxx::identity_t< A > const &a2, ARGS const &...a)`  
*Get the minimum of  $a_1$  and  $a_2$  up to  $a_N$ .*
- `template<typename A, typename ... ARGS>`  
`constexpr A const & cxx::max (A const &a1, A const &a2, ARGS const &...a)`  
*Get the maximum of  $a_1$  and  $a_2$  up to  $a_N$ .*
- `template<typename A, typename ... ARGS>`  
`constexpr A const & cxx::max (cxx::identity_t< A > const &a1, cxx::identity_t< A > const &a2, ARGS const &...a)`  
*Get the maximum of  $a_1$  and  $a_2$  up to  $a_N$ .*
- `template<typename T1>`  
`T1 cxx::clamp (T1 v, T1 lo, T1 hi)`  
*Limit  $v$  to the range given by  $lo$  and  $hi$ .*
- `void * operator new (size_t, void *mem, cxx::Nothrow const &) noexcept`  
*Simple placement new operator.*
- `void * operator new (size_t, cxx::Nothrow const &) noexcept`  
*New operator that does not throw exceptions.*
- `void operator delete (void *, cxx::Nothrow const &) noexcept`  
*Delete operator complementing the new operator not throwing exceptions.*

### 13.14.1 Detailed Description

### 13.14.2 Function Documentation

#### 13.14.2.1 `clamp()`

```
template<typename T1>
T1 cxx::clamp (
    T1 v,
    T1 lo,
    T1 hi) [inline]
```

Limit  $v$  to the range given by  $lo$  and  $hi$ .

#### Parameters

$v$	The value to clamp.
$lo$	The lower boundary to clamp $v$ to.
$hi$	The upper boundary to clamp $v$ to.

Definition at line [109](#) of file [minmax](#).

**13.14.2.2 max()** [1/2]

```
template<typename A, typename ... ARGS>
A const & cxx::max (
    A const & a1,
    A const & a2,
    ARGS const &... a) [constexpr]
```

Get the maximum of a1 and a2 up to aN.

**Parameters**

<i>a1</i>	The first value.
<i>a2</i>	The second value.
<i>...↔ a</i>	Arbitrary number of additional parameters.

Matches with automatic argument type deduction.

Definition at line 78 of file [minmax](#).

**13.14.2.3 max()** [2/2]

```
template<typename A, typename ... ARGS>
A const & cxx::max (
    cxx::identity_t< A > const & a1,
    cxx::identity_t< A > const & a2,
    ARGS const &... a) [constexpr]
```

Get the maximum of a1 and a2 up to aN.

**Parameters**

<i>a1</i>	The first value.
<i>a2</i>	The second value.
<i>...↔ a</i>	Arbitrary number of additional parameters.

Matches with explicit template type A.

Definition at line 93 of file [minmax](#).

**13.14.2.4 min() [1/2]**

```
template<typename A, typename ...  ARGS>
A const & cxx::min (
    A const & a1,
    A const & a2,
    ARGS const &...  a) [constexpr]
```

Get the minimum of a1 and a2 upt to aN.

**Parameters**

<i>a1</i>	The first value.
<i>a2</i>	The second value.
<i>...↔ a</i>	Arbitrary number of additional parameters.

Matches with automatic argument type deduction.

Definition at line 36 of file [minmax](#).

**13.14.2.5 min() [2/2]**

```
template<typename A, typename ...  ARGS>
A const & cxx::min (
    cxx::identity_t< A > const & a1,
    cxx::identity_t< A > const & a2,
    ARGS const &...  a) [constexpr]
```

Get the minimum of a1 and a2 upt to aN.

**Parameters**

<i>a1</i>	The first value.
<i>a2</i>	The second value.
<i>...↔ a</i>	Arbitrary number of additional parameters.

Matches with explicit template type A.

Definition at line 53 of file [minmax](#).

**13.14.2.6 operator new()**

```
void * operator new (
    size_t ,
    void * mem,
    cxx::Nothrow const & ) [inline], [noexcept]
```

Simple placement new operator.

**Parameters**

<i>mem</i>	the address of the memory block to place the new object.
------------	--

**Returns**


the address given by *mem*.

Definition at line 28 of file [std\\_alloc](#).

**13.15 The L4Re IPC Framework**

The mechanisms for IPC communication between [L4Re](#) applications.

Collaboration diagram for The L4Re IPC Framework:

**Topics**

- [Server-Side IPC framework](#) . . . . . 633  
*Server-Side framework for implementing object-oriented servers.*


**13.15.1 Detailed Description**

The mechanisms for IPC communication between [L4Re](#) applications.

**13.15.2 Server-Side IPC framework**

Server-Side framework for implementing object-oriented servers.

Collaboration diagram for Server-Side IPC framework:



## Namespaces

- namespace `L4::lpc_svr`  
*Helper classes for `L4::Server` instantiation.*

## Data Structures

- class `L4::lpc_svr::Server_iface`  
*Interface for server-loop related functions.*
- class `L4::Basic_registry`  
*This registry returns the corresponding server object based on the label of an `lpc_gate`.*
- struct `L4::lpc_svr::Ignore_errors`  
*Mix in for `LOOP_HOOKS` to ignore IPC errors.*
- struct `L4::lpc_svr::Default_timeout`  
*Mix in for `LOOP_HOOKS` to use a 0 send and a infinite receive timeout.*
- struct `L4::lpc_svr::Compound_reply`  
*Mix in for `LOOP_HOOKS` to always use compound reply and wait.*
- struct `L4::lpc_svr::Default_setup_wait`  
*Mix in for `LOOP_HOOKS` for `setup_wait` no op.*
- class `L4::lpc_svr::Br_manager_no_buffers`  
*Empty implementation of `Server_iface`.*
- struct `L4::lpc_svr::Default_loop_hooks`  
*Default `LOOP_HOOKS`.*
- class `L4::Server< LOOP_HOOKS >`  
*Basic server loop for handling client requests.*
- class `L4::Server_object`  
*Abstract server object to be used with `L4::Server` and `L4::Basic_registry`.*
- struct `L4::Server_object_t< IFACE, BASE >`  
*Base class (template) for server implementing server objects.*
- struct `L4::Server_object_x< Derived, IFACE, BASE >`  
*Helper class to implement `p_dispatch` based server objects.*
- struct `L4::lrq_handler_object`  
*`Server` object base class for handling `IRQ` messages.*
- class `L4::lpc_svr::Timeout`  
*Callback interface for `Timeout_queue`.*
- class `L4::lpc_svr::Timeout_queue`  
*`Timeout` queue to be used in `l4re` server loop.*
- class `L4::lpc_svr::Timeout_queue_hooks< HOOKS, BR_MAN >`  
*Loop hooks mixin for integrating a timeout queue into the server loop.*

## Enumerations

- enum `L4::lpc_svr::Reply_mode` { `L4::lpc_svr::Reply_compound` , `L4::lpc_svr::Reply_separate` }  
*Reply mode for server loop.*

### 13.15.2.1 Detailed Description

Server-Side framework for implementing object-oriented servers.

,



### 13.15.2.2 Enumeration Type Documentation

#### 13.15.2.2.1 Reply\_mode

enum [L4::Ipc\\_svr::Reply\\_mode](#)

Reply mode for server loop.

The reply mode specifies if the server loop shall do a compound reply and wait operation ([Reply\\_compound](#)), which is the most performant method. Note, `setup_wait()` is called before the reply. The other way is to call reply and wait separately and call `setup_wait` in between.

The actual mode is determined by the return value of the `before_reply()` hook in the `LOOP_HOOKS` of [L4::Server](#).

#### Enumerator


Reply_compound	<a href="#">Server</a> shall use a compound reply and wait (fast).
Reply_separate	<a href="#">Server</a> shall call reply and wait separately.

Definition at line 46 of file [ipc\\_server\\_loop](#).

## 13.16 Utility Functions

Utilities, generic file.

Collaboration diagram for Utility Functions:



## Topics

- CPU related functions . . . . . [642](#)
- IA32 Port I/O API . . . . . [645](#)
- Timestamp Counter . . . . . [651](#)
-

Atomic Instructions . . . . .	658
•	
Internal functions . . . . .	676
•	
Bit Manipulation . . . . .	676
•	
ELF binary format . . . . .	683
<i>Functions and types related to ELF binaries.</i>	
•	
Kernel Interface Page API . . . . .	708
•	
Comfortable Command Line Parsing . . . . .	710
•	
Random number support . . . . .	712
•	
Low-Level Thread Functions . . . . .	713

## Files

- file [rand.h](#)  
*Simple Pseudo-Random Number Generator.*

## Functions

- [L4\\_BEGIN\\_DECLS](#) long [l4util\\_splitlog2\\_hdl](#) ([l4\\_addr\\_t](#) start, [l4\\_addr\\_t](#) end, long(\*handler)([l4\\_addr\\_t](#) s, [l4\\_addr\\_t](#) e, int log2size))  
*Split a range into log2 base and size aligned chunks.*
- [l4\\_addr\\_t](#) [l4util\\_splitlog2\\_size](#) ([l4\\_addr\\_t](#) start, [l4\\_addr\\_t](#) end)  
*Return log2 base and size aligned length of a range.*
- [L4\\_BEGIN\\_DECLS](#) [l4\\_timeout\\_s](#) [l4util\\_micros2l4to](#) ([l4\\_uint64\\_t](#) us) [L4\\_NOTHROW](#)  
*Calculate l4 timeouts.*
- void [l4\\_sleep](#) ([l4\\_uint32\\_t](#) ms) [L4\\_NOTHROW](#)  
*Suspend thread for a period of ms milliseconds.*
- void [l4\\_usleep](#) ([l4\\_uint64\\_t](#) us) [L4\\_NOTHROW](#)  
*Suspend thread for a period of us microseconds.*
- void [l4\\_sleep\\_forever](#) (void) [L4\\_NOTHROW](#) [L4\\_NORETURN](#)  
*Go sleep and never wake up.*
- void [l4\\_touch\\_ro](#) (const void \*addr, unsigned size) [L4\\_NOTHROW](#)  
*Touch data area to force mapping (read-only).*
- void [l4\\_touch\\_rw](#) (const void \*addr, unsigned size) [L4\\_NOTHROW](#)  
*Touch data areas to force mapping (read-write).*

### 13.16.1 Detailed Description

Utilities, generic file.

## 13.16.2 Function Documentation

### 13.16.2.1 l4\_sleep()

```
void l4_sleep (
    l4_uint32_t ms)
```

Suspend thread for a period of *ms* milliseconds.

#### Parameters

<i>ms</i>	Time in milliseconds
-----------	----------------------


#### Examples

[examples/libs/libirq/async\\_isr.c](#), [examples/sys/aliens/main.c](#), [examples/sys/singlestep/main.c](#), and [examples/sys/start-with-exc/main.c](#).

References [L4\\_CV](#), and [L4\\_NOTHROW](#).

Referenced by [L4Re::Namespace::query\(\)](#).

Here is the caller graph for this function:



### 13.16.2.2 l4\_touch\_ro()

```
void l4_touch_ro (
    const void * addr,
    unsigned size) [inline]
```

Touch data area to force mapping (read-only).

#### Parameters

<i>addr</i>	Start of memory area to touch.
<i>size</i>	Size of area to touch.


#### Examples

[examples/sys/singlestep/main.c](#).

Definition at line 92 of file [util.h](#).

References [L4\\_NOTHROW](#), [L4\\_PAGESIZE](#), and [l4\\_trunc\\_page\(\)](#).

Here is the call graph for this function:



### 13.16.2.3 l4\_touch\_rw()

```
void l4_touch_rw (  
    const void * addr,  
    unsigned size) [inline]
```

Touch data areas to force mapping (read-write).

#### Parameters

<i>addr</i>	Start of memory area to touch.
<i>size</i>	Size of area to touch.

#### Examples

[examples/sys/aliens/main.c](#), and [examples/sys/singlestep/main.c](#).

Definition at line 105 of file [util.h](#).

References [L4\\_NOTHROW](#), [L4\\_PAGESIZE](#), and [l4\\_trunc\\_page\(\)](#).

Here is the call graph for this function:



### 13.16.2.4 l4\_usleep()

```
void l4_usleep (
    l4_uint64_t us)
```

Suspend thread for a period of *us* microseconds.

#### Parameters

<i>us</i>	Time in microseconds
-----------	----------------------

#### Note

The timer resolution of L4 kernels is usually 1ms.

References [L4\\_CV](#), [L4\\_INLINE](#), [L4\\_NORETURN](#), and [L4\\_NOTHROW](#).

### 13.16.2.5 l4util\_micros2l4to()

```
L4_BEGIN_DECLS l4_timeout_s l4util_micros2l4to (
    l4_uint64_t us)
```

Calculate l4 timeouts.

#### Parameters

<i>us</i>	time in microseconds. Special cases: <ul style="list-style-type: none"> <li>• 0 -&gt; timeout 0</li> <li>• ~0U -&gt; timeout NEVER</li> </ul>
-----------	---

#### Returns

the corresponding l4\_timeout value

**Deprecated** Use [l4\\_timeout\\_from\\_us\(\)](#).

References [L4\\_CV](#), and [L4\\_NOTHROW](#).

### 13.16.2.6 l4util\_splitlog2\_hdl()

```
L4_END_DECLS long l4util_splitlog2_hdl (
    l4_addr_t start,
    l4_addr_t end,
    long(* handler ) (l4_addr_t s, l4_addr_t e, int log2size)) [inline]
```

Split a range into log2 base and size aligned chunks.

#### Parameters

<i>start</i>	Start of range
<i>end</i>	End of range (inclusive) (e.g. 2-4 is len 3)
<i>handler</i>	Handler function that is called with start and end (both inclusive) of the chunk. On success, the handler must return 0, if it returns !=0 the function will immediately return with the return code of the handler.

#### Returns

0 on success, != 0 otherwise

Definition at line 51 of file [splitlog2.h](#).

References [L4\\_EINVAL](#), and [l4util\\_splitlog2\\_size\(\)](#).

Here is the call graph for this function:



### 13.16.2.7 l4util\_splitlog2\_size()

```
l4_addr_t l4util_splitlog2_size (
    l4_addr_t start,
    l4_addr_t end) [inline]
```

Return log2 base and size aligned length of a range.

#### Parameters

<i>start</i>	Start of range
<i>end</i>	End of range (inclusive) (e.g. 2-4 is len 3)

**Returns**

length of elements in log2size (length is  $1 \ll \log_2 \text{size}$ )

Definition at line 70 of file [splitlog2.h](#).

Referenced by [l4util\\_splitlog2\\_hdl\(\)](#).

Here is the caller graph for this function:

**13.16.3 CPU related functions**

Collaboration diagram for CPU related functions:

**Functions**

- int [l4util\\_cpu\\_has\\_cpuid](#) (void)  
*Check whether the CPU supports the "cpuid" instruction.*
- unsigned int [l4util\\_cpu\\_capabilities](#) (void)  
*Returns the CPU capabilities if the "cpuid" instruction is available.*
- unsigned int [l4util\\_cpu\\_capabilities\\_nocheck](#) (void)  
*Returns the CPU capabilities.*
- void **`l4util_cpu_cpuid`** (unsigned long mode, unsigned long \*eax, unsigned long \*ebx, unsigned long \*ecx, unsigned long \*edx)  
*Generic CPUID access function.*



### 13.16.3.1 Detailed Description

### 13.16.3.2 Function Documentation

#### 13.16.3.2.1 l4util\_cpu\_capabilities()

```
unsigned int l4util_cpu_capabilities (  
    void ) [inline]
```

Returns the CPU capabilities if the "cpuid" instruction is available.


#### Returns

CPU capabilities if the "cpuid" instruction is available, 0 if the "cpuid" instruction is not supported.

Definition at line 95 of file [cpu.h](#).

References [l4util\\_cpu\\_capabilities\\_nocheck\(\)](#), and [l4util\\_cpu\\_has\\_cpuid\(\)](#).

Here is the call graph for this function:



#### 13.16.3.2.2 l4util\_cpu\_capabilities\_nocheck()

```
unsigned int l4util_cpu_capabilities_nocheck (  
    void ) [inline]
```

Returns the CPU capabilities.

#### Returns


CPU capabilities.

Definition at line 84 of file [cpu.h](#).


References [l4util\\_cpu\\_cpuid\(\)](#).

Referenced by [l4util\\_cpu\\_capabilities\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



#### 13.16.3.2.3 l4util\_cpu\_has\_cpuid()

```
int l4util_cpu_has_cpuid (  
    void ) [inline]
```

Check whether the CPU supports the "cpuid" instruction.

##### Returns

1 if it has, 0 if it has not

Definition at line 64 of file [cpu.h](#).

Referenced by [l4util\\_cpu\\_capabilities\(\)](#).

Here is the caller graph for this function:



### 13.16.4 IA32 Port I/O API

Collaboration diagram for IA32 Port I/O API:



#### Functions

- `l4_uint8_t l4util_in8 (l4_uint16_t port)`  
*Read byte from I/O port.*
- `l4_uint16_t l4util_in16 (l4_uint16_t port)`  
*Read 16-bit-value from I/O port.*
- `l4_uint32_t l4util_in32 (l4_uint16_t port)`  
*Read 32-bit-value from I/O port.*
- `void l4util_ins8 (l4_uint16_t port, l4_umword_t addr, l4_umword_t count)`  
*Read a block of 8-bit-values from I/O ports.*
- `void l4util_ins16 (l4_uint16_t port, l4_umword_t addr, l4_umword_t count)`  
*Read a block of 16-bit-values from I/O ports.*
- `void l4util_ins32 (l4_uint16_t port, l4_umword_t addr, l4_umword_t count)`  
*Read a block of 32-bit-values from I/O ports.*
- `void l4util_out8 (l4_uint8_t value, l4_uint16_t port)`  
*Write byte to I/O port.*
- `void l4util_out16 (l4_uint16_t value, l4_uint16_t port)`  
*Write 16-bit-value to I/O port.*
- `void l4util_out32 (l4_uint32_t value, l4_uint16_t port)`  
*Write 32-bit-value to I/O port.*
- `void l4util_outs8 (l4_uint16_t port, l4_umword_t addr, l4_umword_t count)`  
*Write a block of bytes to I/O port.*
- `void l4util_outs16 (l4_uint16_t port, l4_umword_t addr, l4_umword_t count)`  
*Write a block of 16-bit-values to I/O port.*
- `void l4util_outs32 (l4_uint16_t port, l4_umword_t addr, l4_umword_t count)`  
*Write block of 32-bit-values to I/O port.*
- `void l4util_iodelay (void)`  
*delay I/O port access by writing to port 0x80*
- `int l4util_ioport_map (l4_cap_idx_t sigma0id, unsigned port_start, unsigned log2size)`  
*Map a range of I/O ports.*

### 13.16.4.1 Detailed Description

### 13.16.4.2 Function Documentation

#### 13.16.4.2.1 l4util\_in16()

```
l4_uint16_t l4util_in16 (  
    l4_uint16_t port) [inline]
```

Read 16-bit-value from I/O port.

#### Parameters

<i>port</i>	I/O port address
-------------	------------------

#### Returns

value

Definition at line 195 of file [port\\_io.h](#).

#### 13.16.4.2.2 l4util\_in32()

```
l4_uint32_t l4util_in32 (  
    l4_uint16_t port) [inline]
```

Read 32-bit-value from I/O port.

#### Parameters

<i>port</i>	I/O port address
-------------	------------------

#### Returns

value

Definition at line 203 of file [port\\_io.h](#).

#### 13.16.4.2.3 l4util\_in8()

```
l4_uint8_t l4util_in8 (  
    l4_uint16_t port) [inline]
```

Read byte from I/O port.

##### Parameters

<i>port</i>	I/O port address
-------------	------------------

##### Returns

value

Definition at line 187 of file [port\\_io.h](#).

#### 13.16.4.2.4 l4util\_ins16()

```
void l4util_ins16 (  
    l4_uint16_t port,  
    l4_umword_t addr,  
    l4_umword_t count) [inline]
```

Read a block of 16-bit-values from I/O ports.

##### Parameters

<i>port</i>	I/O port address
<i>addr</i>	address of buffer
<i>count</i>	number of I/O operations

Definition at line 220 of file [port\\_io.h](#).

#### 13.16.4.2.5 l4util\_ins32()

```
void l4util_ins32 (  
    l4_uint16_t port,  
    l4_umword_t addr,  
    l4_umword_t count) [inline]
```

Read a block of 32-bit-values from I/O ports.

##### Parameters

<i>port</i>	I/O port address
<i>addr</i>	address of buffer

<i>count</i>	number of I/O operations
--------------	--------------------------

Definition at line 229 of file [port\\_io.h](#).

#### 13.16.4.2.6 l4util\_ins8()

```
void l4util_ins8 (  
    l4_uint16_t port,  
    l4_umword_t addr,  
    l4_umword_t count) [inline]
```

Read a block of 8-bit-values from I/O ports.

##### Parameters

<i>port</i>	I/O port address
<i>addr</i>	address of buffer
<i>count</i>	number of I/O operations

Definition at line 211 of file [port\\_io.h](#).

#### 13.16.4.2.7 l4util\_ioport\_map()

```
int l4util_ioport_map (  
    l4_cap_idx_t sigma0id,  
    unsigned port_start,  
    unsigned log2size) [inline]
```

Map a range of I/O ports.

##### Parameters

<i>sigma0id</i>	I/O port service (sigma0).
<i>port_start</i>	(Start) Port to request.
<i>log2size</i>	Log2size of range to request.


##### Returns

IPC result: 0 if the range could be successfully mapped on error: IPC failure, or -L4\_ENOENT if nothing mapped

Definition at line 289 of file [port\\_io.h](#).

References [l4\\_buf\\_regs\\_t::bdr](#), [l4\\_buf\\_regs\\_t::br](#), [L4\\_ENOENT](#), [l4\\_iofpage\(\)](#), [l4\\_ipc\\_call\(\)](#), [l4\\_ipc\\_error\(\)](#), [L4\\_IPC\\_NEVER](#), [L4\\_ITEM\\_MAP](#), [l4\\_msgtag\(\)](#), [l4\\_msgtag\\_items\(\)](#), [L4\\_PROTO\\_IO\\_PAGE\\_FAULT](#), [l4\\_utcb\(\)](#), [l4\\_utcb\\_br\(\)](#), [l4\\_utcb\\_mr\(\)](#), [l4\\_msg\\_regs\\_t::mr](#), and [l4\\_fpage\\_t::raw](#).

Here is the call graph for this function:



#### 13.16.4.2.8 l4util\_out16()

```
void l4util_out16 (
    l4_uint16_t value,
    l4_uint16_t port) [inline]
```

Write 16-bit-value to I/O port.

##### Parameters

<i>port</i>	I/O port address
<i>value</i>	value to write

Definition at line 244 of file [port\\_io.h](#).

#### 13.16.4.2.9 l4util\_out32()

```
void l4util_out32 (
    l4_uint32_t value,
    l4_uint16_t port) [inline]
```

Write 32-bit-value to I/O port.

**Parameters**

<i>port</i>	I/O port address
<i>value</i>	value to write

Definition at line 250 of file [port\\_io.h](#).

**13.16.4.2.10 l4util\_out8()**

```
void l4util_out8 (  
    l4_uint8_t value,  
    l4_uint16_t port) [inline]
```

Write byte to I/O port.

**Parameters**

<i>port</i>	I/O port address
<i>value</i>	value to write

Definition at line 238 of file [port\\_io.h](#).

**13.16.4.2.11 l4util\_outs16()**

```
void l4util_outs16 (  
    l4_uint16_t port,  
    l4_umword_t addr,  
    l4_umword_t count) [inline]
```

Write a block of 16-bit-values to I/O port.

**Parameters**

<i>port</i>	I/O port address
<i>addr</i>	address of buffer
<i>count</i>	number of I/O operations

Definition at line 265 of file [port\\_io.h](#).



#### 13.16.4.2.12 l4util\_outs32()

```
void l4util_outs32 (
    l4_uint16_t port,
    l4_umword_t addr,
    l4_umword_t count) [inline]
```

Write block of 32-bit-values to I/O port.

##### Parameters

<i>port</i>	I/O port address
<i>addr</i>	address of buffer
<i>count</i>	number of I/O operations

Definition at line [274](#) of file [port\\_io.h](#).

#### 13.16.4.2.13 l4util\_outs8()

```
void l4util_outs8 (
    l4_uint16_t port,
    l4_umword_t addr,
    l4_umword_t count) [inline]
```

Write a block of bytes to I/O port.


##### Parameters

<i>port</i>	I/O port address
<i>addr</i>	address of buffer
<i>count</i>	number of I/O operations

Definition at line [256](#) of file [port\\_io.h](#).

### 13.16.5 Timestamp Counter

Collaboration diagram for Timestamp Counter:



## Files

- file [rdtsc.h](#)  
*Timestamp counter related functions.*
- file [rdtsc.h](#)  
*Timestamp counter related functions.*

## Functions

- [l4\\_cpu\\_time\\_t l4\\_rdtsc](#) (void)  
*Read current value of CPU-internal timestamp counter.*
- [l4\\_uint32\\_t l4\\_rdtsc\\_32](#) (void)  
*Read the least significant 32 bit of the TSC.*
- [l4\\_uint64\\_t l4\\_rdpmc](#) (int ecx)  
*Return current value of CPU-internal performance measurement counter.*
- [l4\\_uint32\\_t l4\\_rdpmc\\_32](#) (int ecx)  
*Return the least significant 32 bit of a performance counter.*
- [l4\\_uint64\\_t l4\\_tsc\\_to\\_ns](#) ([l4\\_cpu\\_time\\_t](#) tsc)  
*Convert timestamp to ns value.*
- [l4\\_uint64\\_t l4\\_tsc\\_to\\_us](#) ([l4\\_cpu\\_time\\_t](#) tsc)  
*Convert timestamp into micro seconds value.*
- void [l4\\_tsc\\_to\\_s\\_and\\_ns](#) ([l4\\_cpu\\_time\\_t](#) tsc, [l4\\_uint32\\_t](#) \*s, [l4\\_uint32\\_t](#) \*ns)  
*Convert timestamp to s.ns value.*
- [l4\\_cpu\\_time\\_t l4\\_ns\\_to\\_tsc](#) ([l4\\_uint64\\_t](#) ns)  
*Convert nano seconds into CPU ticks.*
- void [l4\\_busy\\_wait\\_ns](#) ([l4\\_uint64\\_t](#) ns)  
*Wait busy for a small amount of time.*
- void [l4\\_busy\\_wait\\_us](#) ([l4\\_uint64\\_t](#) us)  
*Wait busy for a small amount of time.*
- [l4\\_uint32\\_t l4\\_calibrate\\_tsc](#) ([l4\\_kernel\\_info\\_t](#) const \*kip)  
*Determine scalers for timestamp calculations.*
- [l4\\_uint32\\_t l4\\_tsc\\_init](#) ([l4\\_kernel\\_info\\_t](#) const \*kip)  
*Initialize scaler for TSC calibrations from the kernel.*
- [l4\\_uint32\\_t l4\\_get\\_hz](#) (void)  
*Get CPU frequency in Hz.*

### 13.16.5.1 Detailed Description

### 13.16.5.2 Function Documentation

#### 13.16.5.2.1 l4\_busy\_wait\_ns()

```
void l4_busy_wait_ns (
    l4\_uint64\_t ns) [inline]
```

Wait busy for a small amount of time.

**Parameters**

<i>ns</i>	nano seconds to wait
-----------	----------------------


**Attention**

Not intended for any use!

Definition at line 262 of file [rdtsc.h](#).

References [l4\\_ns\\_to\\_tsc\(\)](#), and [l4\\_rdtsc\(\)](#).

Here is the call graph for this function:

**13.16.5.2.2 l4\_busy\_wait\_us()**

```
void l4_busy_wait_us (  
    l4_uint64_t us) [inline]
```

Wait busy for a small amount of time.

**Parameters**

<i>us</i>	micro seconds to wait
-----------	-----------------------


**Attention**

Not intended for any use!

Definition at line 272 of file [rdtsc.h](#).

References [l4\\_ns\\_to\\_tsc\(\)](#), and [l4\\_rdtsc\(\)](#).

Here is the call graph for this function:



### 13.16.5.2.3 l4\_calibrate\_tsc()

```
l4_uint32_t l4_calibrate_tsc (
    l4_kernel_info_t const * kip) [inline]
```

Determine scalars for timestamp calculations.

Determine some scalars to be able to convert between real time and CPU ticks. Just calls [l4\\_tsc\\_init\(\)](#).


#### Examples

[examples/sys/aliens/main.c](#).

Definition at line 159 of file [rdtsc.h](#).

References [l4\\_tsc\\_init\(\)](#).

Here is the call graph for this function:



### 13.16.5.2.4 l4\_get\_hz()

```
l4_uint32_t l4_get_hz (
    void )
```

Get CPU frequency in Hz.

#### Returns

frequency in Hz

References [L4\\_END\\_DECLS](#), and [L4\\_INLINE](#).

#### 13.16.5.2.5 l4\_ns\_to\_tsc()

```
l4_cpu_time_t l4_ns_to_tsc (
    l4_uint64_t ns) [inline]
```

Convert nano seconds into CPU ticks.

##### Parameters

<i>ns</i>	nano seconds
-----------	--------------


##### Returns

CPU ticks

Definition at line 248 of file [rdtsc.h](#).

Referenced by [l4\\_busy\\_wait\\_ns\(\)](#), and [l4\\_busy\\_wait\\_us\(\)](#).

Here is the caller graph for this function:



#### 13.16.5.2.6 l4\_rdpmc()

```
l4_uint64_t l4_rdpmc (
    int ecx) [inline]
```

Return current value of CPU-internal performance measurement counter.

##### Parameters

<i>ecx</i>	ECX value for the rdpmc instruction. For details see the Intel IA-32 Architectures Software Developer's Manual.
------------	---

##### Returns

64-bit PMC

Definition at line 175 of file [rdtsc.h](#).

#### 13.16.5.2.7 l4\_rdpmc\_32()

```
l4_uint32_t l4_rdpmc_32 (
    int ecx) [inline]
```

Return the least significant 32 bit of a performance counter.

Useful for smaller differences, needs less cycles.

Definition at line 195 of file [rdtsc.h](#).

#### 13.16.5.2.8 l4\_rdtsc()

```
l4_cpu_time_t l4_rdtsc (
    void ) [inline]
```

Read current value of CPU-internal timestamp counter.

##### Returns

64-bit timestamp


##### Examples

[examples/sys/aliens/main.c](#).

Definition at line 165 of file [rdtsc.h](#).

Referenced by [l4\\_busy\\_wait\\_ns\(\)](#), and [l4\\_busy\\_wait\\_us\(\)](#).

Here is the caller graph for this function:



#### 13.16.5.2.9 l4\_rdtsc\_32()

```
l4_uint32_t l4_rdtsc_32 (
    void ) [inline]
```

Read the lest significant 32 bit of the TSC.

Useful for smaller differences, needs less cycles.

Definition at line 185 of file [rdtsc.h](#).

**13.16.5.2.10 l4\_tsc\_init()**

```
l4_uint32_t l4_tsc_init (
    l4_kernel_info_t const * kip)
```

Initialize scaler for TSC calibrations from the kernel.

Initialize the scalers needed by [l4\\_tsc\\_to\\_ns\(\)](#)/[l4\\_ns\\_to\\_tsc\(\)](#) and so on. Use the kernel-provided frequency.

**Parameters**

<i>kip</i>	KIP pointer
------------	-------------

**Returns**

0 on error (no scalers exported by kernel) otherwise returns ( $2^{32} / (\text{tsc per } \mu\text{sec})$ ). This value has the same semantics as the value returned by the `calibrate_delay_loop()` function of the Linux kernel.

References [L4\\_CV](#).

Referenced by [l4\\_calibrate\\_tsc\(\)](#).

Here is the caller graph for this function:

**13.16.5.2.11 l4\_tsc\_to\_ns()**

```
l4_uint64_t l4_tsc_to_ns (
    l4_cpu_time_t tsc) [inline]
```

Convert timestamp to ns value.

**Parameters**

<i>tsc</i>	time value in CPU ticks
------------	-------------------------

**Returns**

time value in ns

**Examples**

[examples/sys/aliens/main.c](#).

Definition at line [205](#) of file [rdtsc.h](#).

### 13.16.5.2.12 l4\_tsc\_to\_s\_and\_ns()

```
void l4_tsc_to_s_and_ns (
    l4_cpu_time_t tsc,
    l4_uint32_t * s,
    l4_uint32_t * ns) [inline]
```

Convert timestamp to s.ns value.

#### Parameters

	<i>tsc</i>	time value in CPU ticks
out	<i>s</i>	seconds
out	<i>ns</i>	nano seconds

Definition at line 233 of file [rdtsc.h](#).

### 13.16.5.2.13 l4\_tsc\_to\_us()

```
l4_uint64_t l4_tsc_to_us (
    l4_cpu_time_t tsc) [inline]
```

Convert timestamp into micro seconds value.

#### Parameters

<i>tsc</i>	time value in CPU ticks
------------	-------------------------


#### Returns

time value in micro seconds

Definition at line 219 of file [rdtsc.h](#).

## 13.16.6 Atomic Instructions

Collaboration diagram for Atomic Instructions:





## Files

- file [atomic.h](#)  
*atomic operations header and generic implementations*

## Functions

- `int l4util_cmpxchg32 (volatile l4_uint32_t *dest, l4_uint32_t cmp_val, l4_uint32_t new_val)`  
*Atomic compare and exchange (32 bit version).*
- `int l4util_cmpxchg16 (volatile l4_uint16_t *dest, l4_uint16_t cmp_val, l4_uint16_t new_val)`  
*Atomic compare and exchange (16 bit version).*
- `int l4util_cmpxchg8 (volatile l4_uint8_t *dest, l4_uint8_t cmp_val, l4_uint8_t new_val)`  
*Atomic compare and exchange (8 bit version).*
- `int l4util_cmpxchg (volatile l4_umword_t *dest, l4_umword_t cmp_val, l4_umword_t new_val)`  
*Atomic compare and exchange (machine wide fields).*
- `l4_uint32_t l4util_xchg32 (volatile l4_uint32_t *dest, l4_uint32_t val)`  
*Atomic exchange (32 bit version).*
- `l4_uint16_t l4util_xchg16 (volatile l4_uint16_t *dest, l4_uint16_t val)`  
*Atomic exchange (16 bit version).*
- `l4_uint8_t l4util_xchg8 (volatile l4_uint8_t *dest, l4_uint8_t val)`  
*Atomic exchange (8 bit version).*
- `l4_umword_t l4util_xchg (volatile l4_umword_t *dest, l4_umword_t val)`  
*Atomic exchange (machine wide fields).*
- `void l4util_atomic_add (volatile long *dest, long val)`  
*Atomic add.*
- `void l4util_atomic_inc (volatile long *dest)`  
*Atomic increment.*

### Atomic add/sub/and/or (8,16,32 bit version) without result

- `void l4util_add8 (volatile l4_uint8_t *dest, l4_uint8_t val)`
- `void l4util_add16 (volatile l4_uint16_t *dest, l4_uint16_t val)`
- `void l4util_add32 (volatile l4_uint32_t *dest, l4_uint32_t val)`
- `void l4util_sub8 (volatile l4_uint8_t *dest, l4_uint8_t val)`
- `void l4util_sub16 (volatile l4_uint16_t *dest, l4_uint16_t val)`
- `void l4util_sub32 (volatile l4_uint32_t *dest, l4_uint32_t val)`
- `void l4util_and8 (volatile l4_uint8_t *dest, l4_uint8_t val)`
- `void l4util_and16 (volatile l4_uint16_t *dest, l4_uint16_t val)`
- `void l4util_and32 (volatile l4_uint32_t *dest, l4_uint32_t val)`
- `void l4util_or8 (volatile l4_uint8_t *dest, l4_uint8_t val)`
- `void l4util_or16 (volatile l4_uint16_t *dest, l4_uint16_t val)`
- `void l4util_or32 (volatile l4_uint32_t *dest, l4_uint32_t val)`

### Atomic add/sub/and/or operations (8,16,32 bit) with result

- `l4_uint8_t l4util_add8_res (volatile l4_uint8_t *dest, l4_uint8_t val)`
- `l4_uint16_t l4util_add16_res (volatile l4_uint16_t *dest, l4_uint16_t val)`
- `l4_uint32_t l4util_add32_res (volatile l4_uint32_t *dest, l4_uint32_t val)`
- `l4_uint8_t l4util_sub8_res (volatile l4_uint8_t *dest, l4_uint8_t val)`
- `l4_uint16_t l4util_sub16_res (volatile l4_uint16_t *dest, l4_uint16_t val)`
- `l4_uint32_t l4util_sub32_res (volatile l4_uint32_t *dest, l4_uint32_t val)`
- `l4_uint8_t l4util_and8_res (volatile l4_uint8_t *dest, l4_uint8_t val)`
- `l4_uint16_t l4util_and16_res (volatile l4_uint16_t *dest, l4_uint16_t val)`
- `l4_uint32_t l4util_and32_res (volatile l4_uint32_t *dest, l4_uint32_t val)`
- `l4_uint8_t l4util_or8_res (volatile l4_uint8_t *dest, l4_uint8_t val)`
- `l4_uint16_t l4util_or16_res (volatile l4_uint16_t *dest, l4_uint16_t val)`
- `l4_uint32_t l4util_or32_res (volatile l4_uint32_t *dest, l4_uint32_t val)`

**Atomic inc/dec (8,16,32 bit) without result**

- void [l4util\\_inc8](#) (volatile [l4\\_uint8\\_t](#) \*dest)
- void [l4util\\_inc16](#) (volatile [l4\\_uint16\\_t](#) \*dest)
- void [l4util\\_inc32](#) (volatile [l4\\_uint32\\_t](#) \*dest)
- void [l4util\\_dec8](#) (volatile [l4\\_uint8\\_t](#) \*dest)
- void [l4util\\_dec16](#) (volatile [l4\\_uint16\\_t](#) \*dest)
- void [l4util\\_dec32](#) (volatile [l4\\_uint32\\_t](#) \*dest)

**Atomic inc/dec (8,16,32 bit) with result**

- [l4\\_uint8\\_t](#) [l4util\\_inc8\\_res](#) (volatile [l4\\_uint8\\_t](#) \*dest)
- [l4\\_uint16\\_t](#) [l4util\\_inc16\\_res](#) (volatile [l4\\_uint16\\_t](#) \*dest)
- [l4\\_uint32\\_t](#) [l4util\\_inc32\\_res](#) (volatile [l4\\_uint32\\_t](#) \*dest)
- [l4\\_uint8\\_t](#) [l4util\\_dec8\\_res](#) (volatile [l4\\_uint8\\_t](#) \*dest)
- [l4\\_uint16\\_t](#) [l4util\\_dec16\\_res](#) (volatile [l4\\_uint16\\_t](#) \*dest)
- [l4\\_uint32\\_t](#) [l4util\\_dec32\\_res](#) (volatile [l4\\_uint32\\_t](#) \*dest)

**13.16.6.1 Detailed Description****13.16.6.2 Function Documentation****13.16.6.2.1 l4util\_add16()**

```
void l4util_add16 (
    volatile l4\_uint16\_t * dest,
    l4\_uint16\_t val) [inline]
```

**Parameters**

<i>dest</i>	destination operand
<i>val</i>	value to add/sub/and/or

Definition at line [472](#) of file [atomic.h](#).

**13.16.6.2.2 l4util\_add16\_res()**

```
l4\_uint16\_t l4util_add16_res (
    volatile l4\_uint16\_t * dest,
    l4\_uint16\_t val) [inline]
```

**Parameters**

<i>dest</i>	destination operand
<i>val</i>	value to add/sub/and/or

**Returns**

res

Definition at line [524](#) of file [atomic.h](#).

### 13.16.6.2.3 l4util\_add32()

```
void l4util_add32 (  
    volatile l4_uint32_t * dest,  
    l4_uint32_t val) [inline]
```

#### Parameters

<i>dest</i>	destination operand
<i>val</i>	value to add/sub/and/or

Definition at line 476 of file [atomic.h](#).

### 13.16.6.2.4 l4util\_add32\_res()

```
l4_uint32_t l4util_add32_res (  
    volatile l4_uint32_t * dest,  
    l4_uint32_t val) [inline]
```

#### Parameters

<i>dest</i>	destination operand
<i>val</i>	value to add/sub/and/or

#### Returns

res

Definition at line 528 of file [atomic.h](#).

### 13.16.6.2.5 l4util\_add8()

```
void l4util_add8 (  
    volatile l4_uint8_t * dest,  
    l4_uint8_t val) [inline]
```

#### Parameters

<i>dest</i>	destination operand
<i>val</i>	value to add/sub/and/or

Definition at line 468 of file [atomic.h](#).

#### 13.16.6.2.6 l4util\_add8\_res()

```
l4_uint8_t l4util_add8_res (
    volatile l4_uint8_t * dest,
    l4_uint8_t val) [inline]
```

##### Parameters

<i>dest</i>	destination operand
<i>val</i>	value to add/sub/and/or

##### Returns

res

Definition at line 520 of file [atomic.h](#).

#### 13.16.6.2.7 l4util\_and16()

```
void l4util_and16 (
    volatile l4_uint16_t * dest,
    l4_uint16_t val) [inline]
```

##### Parameters

<i>dest</i>	destination operand
<i>val</i>	value to add/sub/and/or

Definition at line 500 of file [atomic.h](#).

#### 13.16.6.2.8 l4util\_and16\_res()

```
l4_uint16_t l4util_and16_res (
    volatile l4_uint16_t * dest,
    l4_uint16_t val) [inline]
```

##### Parameters

<i>dest</i>	destination operand
<i>val</i>	value to add/sub/and/or

##### Returns

res

Definition at line 548 of file [atomic.h](#).

#### 13.16.6.2.9 l4util\_and32()

```
void l4util_and32 (  
    volatile l4_uint32_t * dest,  
    l4_uint32_t val) [inline]
```

##### Parameters

<i>dest</i>	destination operand
<i>val</i>	value to add/sub/and/or

Definition at line 504 of file [atomic.h](#).

#### 13.16.6.2.10 l4util\_and32\_res()

```
l4_uint32_t l4util_and32_res (  
    volatile l4_uint32_t * dest,  
    l4_uint32_t val) [inline]
```

##### Parameters

<i>dest</i>	destination operand
<i>val</i>	value to add/sub/and/or

##### Returns

res

Definition at line 552 of file [atomic.h](#).

#### 13.16.6.2.11 l4util\_and8()

```
void l4util_and8 (  
    volatile l4_uint8_t * dest,  
    l4_uint8_t val) [inline]
```

##### Parameters

<i>dest</i>	destination operand
<i>val</i>	value to add/sub/and/or

Definition at line 496 of file [atomic.h](#).

### 13.16.6.2.12 l4util\_and8\_res()

```
l4_uint8_t l4util_and8_res (
    volatile l4_uint8_t * dest,
    l4_uint8_t val) [inline]
```

#### Parameters

<i>dest</i>	destination operand
<i>val</i>	value to add/sub/and/or

#### Returns

res

Definition at line 544 of file [atomic.h](#).

### 13.16.6.2.13 l4util\_atomic\_add()

```
void l4util_atomic_add (
    volatile long * dest,
    long val) [inline]
```

Atomic add.

#### Parameters

<i>dest</i>	destination operand
<i>val</i>	value to add

Definition at line 480 of file [atomic.h](#).

### 13.16.6.2.14 l4util\_atomic\_inc()

```
void l4util_atomic_inc (
    volatile long * dest) [inline]
```

Atomic increment.

#### Parameters

<i>dest</i>	destination operand
-------------	---------------------

Definition at line 423 of file [atomic.h](#).

### 13.16.6.2.15 l4util\_cmpxchg()

```
int l4util_cmpxchg (  
    volatile l4_umword_t * dest,  
    l4_umword_t cmp_val,  
    l4_umword_t new_val) [inline]
```

Atomic compare and exchange (machine wide fields).

#### Parameters

<i>dest</i>	destination operand
<i>cmp_val</i>	compare value
<i>new_val</i>	new value for dest

#### Returns


0 if comparison failed, 1 otherwise

Compare the value in *dest* with *cmp\_val*, if equal set *dest* to *new\_val*

Definition at line 379 of file [atomic.h](#).

Referenced by [l4util\\_btr\(\)](#), [l4util\\_bts\(\)](#), [l4util\\_clear\\_bit\(\)](#), and [l4util\\_set\\_bit\(\)](#).

Here is the caller graph for this function:



### 13.16.6.2.16 l4util\_cmpxchg16()

```
int l4util_cmpxchg16 (  
    volatile l4_uint16_t * dest,  
    l4_uint16_t cmp_val,  
    l4_uint16_t new_val) [inline]
```

Atomic compare and exchange (16 bit version).

#### Parameters

<i>dest</i>	destination operand
<i>cmp_val</i>	compare value
<i>new_val</i>	new value for dest

#### Returns

0 if comparison failed, !=0 otherwise

Compare the value in *dest* with *cmp\_val*, if equal set *dest* to *new\_val*

Definition at line 363 of file [atomic.h](#).

### 13.16.6.2.17 l4util\_cmpxchg32()

```
L4_END_DECLS int l4util_cmpxchg32 (  
    volatile l4_uint32_t * dest,  
    l4_uint32_t cmp_val,  
    l4_uint32_t new_val) [inline]
```

Atomic compare and exchange (32 bit version).

#### Parameters

<i>dest</i>	destination operand
<i>cmp_val</i>	compare value
<i>new_val</i>	new value for dest

#### Returns

0 if comparison failed, !=0 otherwise

Compare the value in *dest* with *cmp\_val*, if equal set *dest* to *new\_val*

Definition at line 355 of file [atomic.h](#).



#### 13.16.6.2.18 l4util\_cmpxchg8()

```
int l4util_cmpxchg8 (  
    volatile l4_uint8_t * dest,  
    l4_uint8_t cmp_val,  
    l4_uint8_t new_val) [inline]
```

Atomic compare and exchange (8 bit version).

##### Parameters

<i>dest</i>	destination operand
<i>cmp_val</i>	compare value
<i>new_val</i>	new value for dest

##### Returns

0 if comparison failed, !=0 otherwise

Compare the value in *dest* with *cmp\_val*, if equal set *dest* to *new\_val*

Definition at line 371 of file [atomic.h](#).

#### 13.16.6.2.19 l4util\_dec16()

```
void l4util_dec16 (  
    volatile l4_uint16_t * dest) [inline]
```

##### Parameters

<i>dest</i>	destination operand
-------------	---------------------

Definition at line 431 of file [atomic.h](#).

#### 13.16.6.2.20 l4util\_dec16\_res()

```
l4_uint16_t l4util_dec16_res (  
    volatile l4_uint16_t * dest) [inline]
```

##### Parameters

<i>dest</i>	destination operand
-------------	---------------------

##### Returns

res

Definition at line 456 of file [atomic.h](#).

#### 13.16.6.2.21 l4util\_dec32()

```
void l4util_dec32 (  
    volatile l4_uint32_t * dest) [inline]
```

##### Parameters

<i>dest</i>	destination operand
-------------	---------------------

Definition at line 435 of file [atomic.h](#).

#### 13.16.6.2.22 l4util\_dec32\_res()

```
l4_uint32_t l4util_dec32_res (  
    volatile l4_uint32_t * dest) [inline]
```

##### Parameters

<i>dest</i>	destination operand
-------------	---------------------

##### Returns

res

Definition at line 460 of file [atomic.h](#).

#### 13.16.6.2.23 l4util\_dec8()

```
void l4util_dec8 (  
    volatile l4_uint8_t * dest) [inline]
```

##### Parameters

<i>dest</i>	destination operand
-------------	---------------------

Definition at line 427 of file [atomic.h](#).

#### 13.16.6.2.24 l4util\_dec8\_res()

```
l4_uint8_t l4util_dec8_res (  
    volatile l4_uint8_t * dest) [inline]
```

##### Parameters

<i>dest</i>	destination operand
-------------	---------------------

##### Returns

res

Definition at line 452 of file [atomic.h](#).

#### 13.16.6.2.25 l4util\_inc16()

```
void l4util_inc16 (
    volatile l4_uint16_t * dest) [inline]
```

##### Parameters

<i>dest</i>	destination operand
-------------	---------------------

Definition at line 415 of file [atomic.h](#).

#### 13.16.6.2.26 l4util\_inc16\_res()

```
l4_uint16_t l4util_inc16_res (
    volatile l4_uint16_t * dest) [inline]
```

##### Parameters

<i>dest</i>	destination operand
-------------	---------------------

##### Returns

res

Definition at line 444 of file [atomic.h](#).

#### 13.16.6.2.27 l4util\_inc32()

```
void l4util_inc32 (
    volatile l4_uint32_t * dest) [inline]
```

##### Parameters

<i>dest</i>	destination operand
-------------	---------------------

Definition at line 419 of file [atomic.h](#).

#### 13.16.6.2.28 l4util\_inc32\_res()

```
l4_uint32_t l4util_inc32_res (
    volatile l4_uint32_t * dest) [inline]
```

##### Parameters

---

<i>dest</i>	destination operand
-------------	---------------------

**Returns**

res

Definition at line 448 of file [atomic.h](#).

**13.16.6.2.29 l4util\_inc8()**

```
void l4util_inc8 (  
    volatile l4_uint8_t * dest) [inline]
```

**Parameters**

<i>dest</i>	destination operand
-------------	---------------------

Definition at line 411 of file [atomic.h](#).

**13.16.6.2.30 l4util\_inc8\_res()**

```
l4_uint8_t l4util_inc8_res (  
    volatile l4_uint8_t * dest) [inline]
```

**Parameters**

<i>dest</i>	destination operand
-------------	---------------------

**Returns**

res

Definition at line 440 of file [atomic.h](#).

**13.16.6.2.31 l4util\_or16()**

```
void l4util_or16 (  
    volatile l4_uint16_t * dest,  
    l4_uint16_t val) [inline]
```

**Parameters**

<i>dest</i>	destination operand
-------------	---------------------

<i>val</i>	value to add/sub/and/or
------------	-------------------------

Definition at line 512 of file [atomic.h](#).

#### 13.16.6.2.32 l4util\_or16\_res()

```
l4_uint16_t l4util_or16_res (  
    volatile l4_uint16_t * dest,  
    l4_uint16_t val) [inline]
```

##### Parameters

<i>dest</i>	destination operand
<i>val</i>	value to add/sub/and/or

##### Returns

res

Definition at line 560 of file [atomic.h](#).

#### 13.16.6.2.33 l4util\_or32()

```
void l4util_or32 (  
    volatile l4_uint32_t * dest,  
    l4_uint32_t val) [inline]
```

##### Parameters

<i>dest</i>	destination operand
<i>val</i>	value to add/sub/and/or

Definition at line 516 of file [atomic.h](#).

#### 13.16.6.2.34 l4util\_or32\_res()

```
l4_uint32_t l4util_or32_res (  
    volatile l4_uint32_t * dest,  
    l4_uint32_t val) [inline]
```

##### Parameters

<i>dest</i>	destination operand
<i>val</i>	value to add/sub/and/or

##### Returns

res

Definition at line 564 of file [atomic.h](#).

#### 13.16.6.2.35 l4util\_or8()

```
void l4util_or8 (
    volatile l4_uint8_t * dest,
    l4_uint8_t val) [inline]
```

##### Parameters

<i>dest</i>	destination operand
<i>val</i>	value to add/sub/and/or

Definition at line 508 of file [atomic.h](#).

#### 13.16.6.2.36 l4util\_or8\_res()

```
l4_uint8_t l4util_or8_res (
    volatile l4_uint8_t * dest,
    l4_uint8_t val) [inline]
```

##### Parameters

<i>dest</i>	destination operand
<i>val</i>	value to add/sub/and/or

##### Returns

res

Definition at line 556 of file [atomic.h](#).

#### 13.16.6.2.37 l4util\_sub16()

```
void l4util_sub16 (
    volatile l4_uint16_t * dest,
    l4_uint16_t val) [inline]
```

##### Parameters

<i>dest</i>	destination operand
<i>val</i>	value to add/sub/and/or

Definition at line 488 of file [atomic.h](#).

**13.16.6.2.38 l4util\_sub16\_res()**

```
l4_uint16_t l4util_sub16_res (  
    volatile l4_uint16_t * dest,  
    l4_uint16_t val) [inline]
```

**Parameters**

<i>dest</i>	destination operand
<i>val</i>	value to add/sub/and/or

**Returns**

res

Definition at line 536 of file [atomic.h](#).

**13.16.6.2.39 l4util\_sub32()**

```
void l4util_sub32 (  
    volatile l4_uint32_t * dest,  
    l4_uint32_t val) [inline]
```

**Parameters**

<i>dest</i>	destination operand
<i>val</i>	value to add/sub/and/or

Definition at line 492 of file [atomic.h](#).

**13.16.6.2.40 l4util\_sub32\_res()**

```
l4_uint32_t l4util_sub32_res (  
    volatile l4_uint32_t * dest,  
    l4_uint32_t val) [inline]
```

**Parameters**

<i>dest</i>	destination operand
<i>val</i>	value to add/sub/and/or

**Returns**

res

Definition at line 540 of file [atomic.h](#).

#### 13.16.6.2.41 l4util\_sub8()

```
void l4util_sub8 (
    volatile l4_uint8_t * dest,
    l4_uint8_t val) [inline]
```

##### Parameters

<i>dest</i>	destination operand
<i>val</i>	value to add/sub/and/or

Definition at line 484 of file [atomic.h](#).

#### 13.16.6.2.42 l4util\_sub8\_res()

```
l4_uint8_t l4util_sub8_res (
    volatile l4_uint8_t * dest,
    l4_uint8_t val) [inline]
```

##### Parameters

<i>dest</i>	destination operand
<i>val</i>	value to add/sub/and/or

##### Returns

res

Definition at line 532 of file [atomic.h](#).

#### 13.16.6.2.43 l4util\_xchg()

```
l4_umword_t l4util_xchg (
    volatile l4_umword_t * dest,
    l4_umword_t val) [inline]
```

Atomic exchange (machine wide fields).

##### Parameters

<i>dest</i>	destination operand
<i>val</i>	new value for dest

##### Returns

old value at destination

Definition at line 405 of file [atomic.h](#).



**13.16.6.2.44 l4util\_xchg16()**

```
l4_uint16_t l4util_xchg16 (
    volatile l4_uint16_t * dest,
    l4_uint16_t val) [inline]
```

Atomic exchange (16 bit version).

**Parameters**

<i>dest</i>	destination operand
<i>val</i>	new value for dest

**Returns**

old value at destination

Definition at line 393 of file [atomic.h](#).

**13.16.6.2.45 l4util\_xchg32()**

```
l4_uint32_t l4util_xchg32 (
    volatile l4_uint32_t * dest,
    l4_uint32_t val) [inline]
```

Atomic exchange (32 bit version).

**Parameters**

<i>dest</i>	destination operand
<i>val</i>	new value for dest

**Returns**

old value at destination

Definition at line 387 of file [atomic.h](#).

**13.16.6.2.46 l4util\_xchg8()**

```
l4_uint8_t l4util_xchg8 (
    volatile l4_uint8_t * dest,
    l4_uint8_t val) [inline]
```

Atomic exchange (8 bit version).

### Parameters

<i>dest</i>	destination operand
<i>val</i>	new value for dest

### Returns

old value at destination

Definition at line 399 of file [atomic.h](#).

## 13.16.7 Internal functions

Collaboration diagram for Internal functions:



### Functions

- void **base64\_encode** (const char \*infile, unsigned int in\_size, char \*\*outfile)  
*base-64-encode string infile*
- void **base64\_decode** (const char \*infile, unsigned int in\_size, char \*\*outfile)  
*decode base-64-encoded string infile*

### 13.16.7.1 Detailed Description

## 13.16.8 Bit Manipulation

Collaboration diagram for Bit Manipulation:



## Files

- file [bitops\\_arch.h](#)  
*amd64 bit manipulation functions*
- file [bitops.h](#)  
*bit manipulation functions*
- file [bitops\\_arch.h](#)  
*x86 bit manipulation functions*

## Functions

- void [l4util\\_set\\_bit](#) (int b, volatile [l4\\_umword\\_t](#) \*dest)  
*Set bit in memory.*
- void [l4util\\_clear\\_bit](#) (int b, volatile [l4\\_umword\\_t](#) \*dest)  
*Clear bit in memory.*
- void [l4util\\_complement\\_bit](#) (int b, volatile [l4\\_umword\\_t](#) \*dest)  
*Complement bit in memory.*
- int [l4util\\_test\\_bit](#) (int b, const volatile [l4\\_umword\\_t](#) \*dest)  
*Test bit (return value of bit).*
- int [l4util\\_bts](#) (int b, volatile [l4\\_umword\\_t](#) \*dest)  
*Bit test and set.*
- int [l4util\\_btr](#) (int b, volatile [l4\\_umword\\_t](#) \*dest)  
*Bit test and reset.*
- int [l4util\\_btc](#) (int b, volatile [l4\\_umword\\_t](#) \*dest)  
*Bit test and complement.*
- int [l4util\\_bsr](#) ([l4\\_umword\\_t](#) word)  
*Bit scan reverse.*
- int [l4util\\_bsf](#) ([l4\\_umword\\_t](#) word)  
*Bit scan forward.*
- int [l4util\\_find\\_first\\_set\\_bit](#) (const void \*dest, [l4\\_size\\_t](#) size)  
*Find the first set bit in a memory region.*
- int [l4util\\_find\\_first\\_zero\\_bit](#) (const void \*dest, [l4\\_size\\_t](#) size)  
*Find the first zero bit in a memory region.*
- int [l4util\\_next\\_power2](#) (unsigned long val)  
*Find the next power of 2 for a given number.*

### 13.16.8.1 Detailed Description

### 13.16.8.2 Function Documentation

#### 13.16.8.2.1 l4util\_bsf()

```
int l4util_bsf (
    l4\_umword\_t word) [inline]
```

Bit scan forward.

**Parameters**

<i>word</i>	value (machine size)
-------------	----------------------

**Returns**

index of least significant bit set in word, -1 if no bit is set (word == 0)

"bit scan forward", find least significant bit set in word.

Definition at line 316 of file [bitops.h](#).

**13.16.8.2.2 l4util\_bsr()**

```
int l4util_bsr (
    l4_umword_t word) [inline]
```

Bit scan reverse.

**Parameters**

<i>word</i>	value (machine size)
-------------	----------------------

**Returns**

index of most significant set bit in word, -1 if no bit is set (word == 0)

"bit scan reverse", find most significant set bit in word (-> LOG2(word))

Definition at line 299 of file [bitops.h](#).

**13.16.8.2.3 l4util\_btc()**

```
int l4util_btc (
    int b,
    volatile l4_umword_t * dest) [inline]
```

Bit test and complement.

**Parameters**

<i>b</i>	bit position
<i>dest</i>	destination operand

**Returns**

Old value of bit *b*.

Complement bit *b* and return old value.

Definition at line 394 of file [bitops.h](#).

#### 13.16.8.2.4 l4util\_btr()

```
int l4util_btr (  
    int b,  
    volatile l4_umword_t * dest) [inline]
```

Bit test and reset.

##### Parameters

<i>b</i>	bit position
<i>dest</i>	destination operand

##### Returns


Old value of bit *b*.

Reset bit *b* and return old value.

Definition at line 278 of file [bitops.h](#).

References [l4util\\_cmpxchg\(\)](#).

Here is the call graph for this function:



#### 13.16.8.2.5 l4util\_bts()

```
int l4util_bts (  
    int b,  
    volatile l4_umword_t * dest) [inline]
```

Bit test and set.

##### Parameters

<i>b</i>	bit position
<i>dest</i>	destination operand

**Returns**


Old value of bit *b*.

Set the *b* bit of *dest* to 1 and return the old value.

Definition at line 256 of file [bitops.h](#).

References [l4util\\_cmpxchg\(\)](#).

Here is the call graph for this function:

**13.16.8.2.6 l4util\_clear\_bit()**

```
void l4util_clear_bit (  
    int b,  
    volatile l4_umword_t * dest) [inline]
```

Clear bit in memory.

**Parameters**

<i>b</i>	bit position
<i>dest</i>	destination operand

Definition at line 226 of file [bitops.h](#).

References [l4util\\_cmpxchg\(\)](#).

Here is the call graph for this function:



### 13.16.8.2.7 l4util\_complement\_bit()

```
void l4util_complement_bit (
    int b,
    volatile l4_umword_t * dest) [inline]
```

Complement bit in memory.

#### Parameters

<i>b</i>	bit position
<i>dest</i>	destination operand

Definition at line 359 of file [bitops.h](#).

### 13.16.8.2.8 l4util\_find\_first\_set\_bit()

```
int l4util_find_first_set_bit (
    const void * dest,
    l4_size_t size) [inline]
```

Find the first set bit in a memory region.

#### Parameters

<i>dest</i>	bit string
<i>size</i>	size of string in bits (must be a multiple of L4_MWORD_BITS!)

#### Returns

number of the first set bit, >= size if no bit is set

Definition at line 400 of file [bitops.h](#).

### 13.16.8.2.9 l4util\_find\_first\_zero\_bit()

```
int l4util_find_first_zero_bit (
    const void * dest,
    l4_size_t size) [inline]
```

Find the first zero bit in a memory region.

#### Parameters

<i>dest</i>	bit string
<i>size</i>	size of string in bits (must be a multiple of L4_MWORD_BITS!)

#### Returns

number of the first zero bit, >= size if no bit is set

Definition at line 333 of file [bitops.h](#).

### 13.16.8.2.10 l4util\_next\_power2()

```
int l4util_next_power2 (  
    unsigned long val) [inline]
```

Find the next power of 2 for a given number.

#### Parameters

<i>val</i>	initial value
------------	---------------

#### Returns

next-highest power of 2

Definition at line 373 of file [bitops.h](#).

### 13.16.8.2.11 l4util\_set\_bit()

```
void l4util_set_bit (  
    int b,  
    volatile l4_umword_t * dest) [inline]
```

Set bit in memory.

#### Parameters

<i>b</i>	bit position
<i>dest</i>	destination operand

Definition at line 207 of file [bitops.h](#).

References [l4util\\_cmpxchg\(\)](#).

Here is the call graph for this function:





#### 13.16.8.2.12 l4util\_test\_bit()

```
int l4util_test_bit (
    int b,
    const volatile l4_umword_t * dest) [inline]
```

Test bit (return value of bit).

##### Parameters

<i>b</i>	bit position
<i>dest</i>	destination operand

##### Returns

Value of bit *b*.

Definition at line 244 of file [bitops.h](#).

### 13.16.9 ELF binary format

Functions and types related to ELF binaries.

Collaboration diagram for ELF binary format:



##### Files

- file [elf.h](#)  
*ELF definition.*

##### Data Structures

- struct [Elf32\\_Ehdr](#)  
*ELF32 header.*
- struct [Elf64\\_Ehdr](#)  
*ELF64 header.*
- struct [Elf32\\_Shdr](#)  
*ELF32 section header.*
- struct [Elf64\\_Shdr](#)

- ELF64 section header.*
- struct [Elf32\\_Phdr](#)
  - ELF32 program header.*
- struct [Elf64\\_Phdr](#)
  - ELF64 program header.*
- struct [Elf32\\_Dyn](#)
  - ELF32 dynamic entry.*
- struct [Elf64\\_Dyn](#)
  - ELF64 dynamic entry.*
- struct [Elf32\\_Rel](#)
  - ELF32 relocation entry w/o addend.*
- struct [Elf32\\_Rela](#)
  - ELF32 relocation entry w/ addend.*
- struct [Elf64\\_Rel](#)
  - ELF64 relocation entry w/o addend.*
- struct [Elf64\\_Rela](#)
  - ELF64 relocation entry w/ addend.*
- struct [Elf32\\_Sym](#)
  - ELF32 symbol table entry.*
- struct [Elf64\\_Sym](#)
  - ELF64 symbol table entry.*
- struct [Elf32\\_Auxv](#)
  - Auxiliary vector (32-bit).*
- struct [Elf64\\_Auxv](#)
  - Auxiliary vector (64-bit).*

## Macros

- #define **ElfW**(type)
  - Use 64 or 32 bits types depending on the target architecture.*
- #define **ELF32\_R\_SYM**(i)
  - Symbol table index.*
- #define **ELF32\_R\_TYPE**(i)
- #define **ELF32\_R\_INFO**(s, t)
  - Create info from symbol table index + type.*
- #define **ELF64\_R\_SYM**(i)
  - Symbol table index.*
- #define **ELF64\_R\_TYPE**(i)
- #define **ELF64\_R\_INFO**(s, t)
  - Create info from symbol table index + type.*
- #define **ELF32\_ST\_BIND**(i)
- #define **ELF32\_ST\_TYPE**(i)
- #define **ELF32\_ST\_INFO**(b, t)
  - Make info from bind + type.*
- #define **ELF64\_ST\_BIND**(i)
- #define **ELF64\_ST\_TYPE**(i)
- #define **ELF64\_ST\_INFO**(b, t)
  - Make info from bind + type.*

## Typedefs

- typedef struct Elf32\_Auxv **Elf32\_Auxv**  
*Auxiliary vector (32-bit).*
- typedef struct Elf64\_Auxv **Elf64\_Auxv**  
*Auxiliary vector (64-bit).*

## Enumerations

- enum { **EI\_NIDENT** = 16 }
- enum **Elf\_ETs** {  
  **ET\_NONE** = 0 , **ET\_REL** = 1 , **ET\_EXEC** = 2 , **ET\_DYN** = 3 ,  
  **ET\_CORE** = 4 , **ET\_LOPROC** = 0xff00 , **ET\_HIPROC** = 0xffff }
- Object file type.*
- enum **Elf\_EMs** {  
  **EM\_NONE** = 0 , **EM\_M32** = 1 , **EM\_SPARC** = 2 , **EM\_386** = 3 ,  
  **EM\_68K** = 4 , **EM\_88K** = 5 , **EM\_860** = 7 , **EM\_MIPS** = 8 ,  
  **EM\_MIPS\_RS4\_BE** = 10 , **EM\_SPARC64** = 11 , **EM\_PARISC** = 15 , **EM\_VPP500** = 17 ,  
  **EM\_SPARC32PLUS** = 18 , **EM\_960** = 19 , **EM\_PPC** = 20 , **EM\_V800** = 36 ,  
  **EM\_FR20** = 37 , **EM\_RH32** = 38 , **EM\_RCE** = 39 , **EM\_ARM** = 40 ,  
  **EM\_ALPHA** = 41 , **EM\_SH** = 42 , **EM\_SPARCV9** = 43 , **EM\_TRICORE** = 44 ,  
  **EM\_ARC** = 45 , **EM\_H8\_300** = 46 , **EM\_H8\_300H** = 47 , **EM\_H8S** = 48 ,  
  **EM\_H8\_500** = 49 , **EM\_IA\_64** = 50 , **EM\_MIPS\_X** = 51 , **EM\_COLDFIRE** = 52 ,  
  **EM\_68HC12** = 53 , **EM\_X86\_64** = 62 , **EM\_PDSP** = 63 , **EM\_FX66** = 66 ,  
  **EM\_ST9PLUS** = 67 , **EM\_ST7** = 68 , **EM\_68HC16** = 69 , **EM\_68HC11** = 70 ,  
  **EM\_68HC08** = 71 , **EM\_68HC05** = 72 , **EM\_SVX** = 73 , **EM\_ST19** = 74 ,  
  **EM\_VAX** = 75 , **EM\_CRIS** = 76 , **EM\_JAVELIN** = 77 , **EM\_FIREPATH** = 78 ,  
  **EM\_ZSP** = 79 , **EM\_MMIX** = 80 , **EM\_HUANY** = 81 , **EM\_PRISM** = 82 ,  
  **EM\_AVR** = 83 , **EM\_FR30** = 84 , **EM\_D10V** = 85 , **EM\_D30V** = 86 ,  
  **EM\_V850** = 87 , **EM\_M32R** = 88 , **EM\_MN10300** = 89 , **EM\_MN10200** = 90 ,  
  **EM\_PJ** = 91 , **EM\_OPENRISC** = 92 , **EM\_ARC\_A5** = 93 , **EM\_XTENSA** = 94 ,  
  **EM\_ALTERA\_NIOS2** = 113 , **EM\_AARCH64** = 183 , **EM\_TILEPRO** = 188 , **EM\_MICROBLAZE** = 189 ,  
  **EM\_TILEGX** = 191 , **EM\_RISCV** = 243 , **EM\_NUM** = 244 }
- Required architecture.*
- enum **Elf\_EVs** { **EV\_NONE** = 0 , **EV\_CURRENT** = 1 }
- Object file version.*
- enum **Elf\_EIs** {  
  **EI\_MAG0** = 0 , **EI\_MAG1** = 1 , **EI\_MAG2** = 2 , **EI\_MAG3** = 3 ,  
  **EI\_CLASS** = 4 , **EI\_DATA** = 5 , **EI\_VERSION** = 6 , **EI\_OSABI** = 7 ,  
  **EI\_ABIVERSION** = 8 , **EI\_PAD** = 9 }
- Identification Indices.*
- enum **Elf\_MAGs** { **ELFMAG0** = 0x7f , **ELFMAG1** = 'E' , **ELFMAG2** = 'L' , **ELFMAG3** = 'F' }
- Magic number.*
- enum **Elf\_CLASSs** { **ELFCLASSNONE** = 0 , **ELFCLASS32** = 1 , **ELFCLASS64** = 2 , **ELFCLASSNUM** = 3 }
- File class or capacity.*
- enum **Elf\_DATAs** { **ELFDATANONE** = 0 , **ELFDATA2LSB** = 1 , **ELFDATA2MSB** = 2 , **ELFDATANUM** = 3 }
- Data encoding.*
- enum **Elf\_OSABIs** {  
  **ELFOSABI\_NONE** = 0 , **ELFOSABI\_SYSV** = 0 , **ELFOSABI\_HPUX** = 1 , **ELFOSABI\_NETBSD** = 2 ,  
  **ELFOSABI\_LINUX** = 3 , **ELFOSABI\_SOLARIS** = 6 , **ELFOSABI\_AIX** = 7 , **ELFOSABI\_IRIX** = 8 ,  
  **ELFOSABI\_FREEBSD** = 9 , **ELFOSABI\_TRU64** = 10 , **ELFOSABI\_MODESTO** = 11 , **ELFOSABI\_OPENBSD** = 12 ,  
  **ELFOSABI\_ARM** = 97 , **ELFOSABI\_STANDALONE** = 255 }
- Identify operating system and ABI to which the object is targeted.*

- enum `Elf_SHNs` {  
`SHN_UNDEF` = 0 , `SHN_LORESERVE` = 0xff00 , `SHN_LOPROC` = 0xff00 , `SHN_HIPROC` = 0xff1f ,  
`SHN_ABS` = 0xffff , `SHN_COMMON` = 0xffff2 , `SHN_HIRESERVE` = 0xffff }  
*Special section indexes.*
- enum `Elf_SHTs` {  
`SHT_NULL` = 0 , `SHT_PROGBITS` = 1 , `SHT_SYMTAB` = 2 , `SHT_STRTAB` = 3 ,  
`SHT_RELA` = 4 , `SHT_HASH` = 5 , `SHT_DYNAMIC` = 6 , `SHT_NOTE` = 7 ,  
`SHT_NOBITS` = 8 , `SHT_REL` = 9 , `SHT_SHLIB` = 10 , `SHT_DYNSYM` = 11 ,  
`SHT_INIT_ARRAY` = 14 , `SHT_FINI_ARRAY` = 15 , `SHT_PREINIT_ARRAY` = 16 , `SHT_GROUP` = 17 ,  
`SHT_SYMTAB_SHNDX` = 18 , `SHT_NUM` = 19 , `SHT_LOOS` = 0x60000000 , `SHT_HIOS` = 0x6fffffff ,  
`SHT_LOPROC` = 0x70000000 , `SHT_HIPROC` = 0x7fffffff , `SHT_LOUSER` = 0x80000000 , `SHT_HIUSER` =  
0xffffffff }  
*Section type.*
- enum `Elf_SHFs` {  
`SHF_WRITE` = 0x1 , `SHF_ALLOC` = 0x2 , `SHF_EXECINSTR` = 0x4 , `SHF_MERGE` = 0x10 ,  
`SHF_STRINGS` = 0x20 , `SHF_INFO_LINK` = 0x40 , `SHF_LINK_ORDER` = 0x80 , `SHF_OS_NONCONFORMING`  
= 0x100 ,  
`SHF_GROUP` = 0x200 , `SHF_TLS` = 0x400 , `SHF_MASKOS` = 0x0ff00000 , `SHF_MASKPROC` = 0xf0000000  
}  
*Section attribute flags.*
- enum `Elf_PTs` {  
`PT_NULL` = 0 , `PT_LOAD` = 1 , `PT_DYNAMIC` = 2 , `PT_INTERP` = 3 ,  
`PT_NOTE` = 4 , `PT_SHLIB` = 5 , `PT_PHDR` = 6 , `PT_TLS` = 7 ,  
`PT_NUM` = 8 , `PT_LOOS` = 0x60000000 , `PT_HIOS` = 0x6fffffff , `PT_LOPROC` = 0x70000000 ,  
`PT_HIPROC` = 0x7fffffff , `PT_GNU_EH_FRAME` = `PT_LOOS` + 0x474e550 , `PT_GNU_STACK` = `PT_LOOS`  
+ 0x474e551 , `PT_GNU_RELRO` = `PT_LOOS` + 0x474e552 ,  
`PT_L4_STACK` = `PT_LOOS` + 0x12 , `PT_L4_AUX` = `PT_LOOS` + 0x14 }  
*Segment types.*
- enum `Elf_PFs` {  
`PF_X` = 0x1 , `PF_W` = 0x2 , `PF_R` = 0x4 , `PF_MASKOS` = 0x0ff00000 ,  
`PF_MASKPROC` = 0x7fffffff }  
*Segment permissions.*
- enum `Elf_NTscore` {  
`NT_PRSTATUS` = 1 , `NT_FPREGSET` = 2 , `NT_PRPSINFO` = 3 , `NT_PRXREG` = 4 ,  
`NT_TASKSTRUCT` = 4 , `NT_PLATFORM` = 5 , `NT_AUXV` = 6 , `NT_GWINDOWS` = 7 ,  
`NT_ASRS` = 8 , `NT_PSTATUS` = 10 , `NT_PSINFO` = 13 , `NT_PRCRED` = 14 ,  
`NT_UTSNAME` = 15 , `NT_LWPSTATUS` = 16 , `NT_LWPSINFO` = 17 , `NT_PRFPXREG` = 20 }  
*Legal values for note segment descriptor types for core files.*
- enum `Elf_NTsobj` { `NT_VERSION` = 1 }  
*Legal values for the note segment descriptor types for object files.*
- enum `Elf_DTsc` {  
`DT_NULL` = 0 , `DT_NEEDED` = 1 , `DT_PLTRELSZ` = 2 , `DT_PLTGOT` = 3 ,  
`DT_HASH` = 4 , `DT_STRTAB` = 5 , `DT_SYMTAB` = 6 , `DT_RELA` = 7 ,  
`DT_RELASZ` = 8 , `DT_RELAENT` = 9 , `DT_STRSZ` = 10 , `DT_SYMENT` = 11 ,  
`DT_INIT` = 12 , `DT_FINI` = 13 , `DT_SONAME` = 14 , `DT_RPATH` = 15 ,  
`DT_SYMBOLIC` = 16 , `DT_REL` = 17 , `DT_RELSZ` = 18 , `DT_RELENT` = 19 ,  
`DT_PTRREL` = 20 , `DT_DEBUG` = 21 , `DT_TEXTREL` = 22 , `DT_JMPREL` = 23 ,  
`DT_BIND_NOW` = 24 , `DT_INIT_ARRAY` = 25 , `DT_FINI_ARRAY` = 26 , `DT_INIT_ARRAYSZ` = 27 ,  
`DT_FINI_ARRAYSZ` = 28 , `DT_RUNPATH` = 29 , `DT_FLAGS` = 30 , `DT_ENCODING` = 32 ,  
`DT_PREINIT_ARRAY` = 32 , `DT_PREINIT_ARRAYSZ` = 33 , `DT_NUM` = 34 , `DT_LOOS` = 0x6000000d ,  
`DT_HIOS` = 0x6ffff000 , `DT_LOPROC` = 0x70000000 , `DT_HIPROC` = 0x7fffffff }  
*Dynamic Array Tags.*
- enum `Elf_DFs` {  
`DF_ORIGIN` = 0x00000001 , `DF_SYMBOLIC` = 0x00000002 , `DF_TEXTREL` = 0x00000004 ,  
`DF_BIND_NOW` = 0x00000008 ,  
`DF_STATIC_TLS` = 0x00000010 }

*Values of Elf32\_Dyn.d\_un.d\_val, Elf64\_Dyn.d\_un.d\_val in the DT\_FLAGS entry.*

- enum `Elf_DF_1s` {  
`DF_1_NOW` = 0x00000001 , `DF_1_GLOBAL` = 0x00000002 , `DF_1_GROUP` = 0x00000004 ,  
`DF_1_NODELETE` = 0x00000008 ,  
`DF_1_LOADFLTR` = 0x00000010 , `DF_1_INITFIRST` = 0x00000020 , `DF_1_NOOPEN` = 0x00000040 ,  
`DF_1_ORIGIN` = 0x00000080 ,  
`DF_1_DIRECT` = 0x00000100 , `DF_1_TRANS` = 0x00000200 , `DF_1_INTERPOSE` = 0x00000400 ,  
`DF_1_NODEFLIB` = 0x00000800 ,  
`DF_1_NODUMP` = 0x00001000 , `DF_1_CONFALT` = 0x00002000 , `DF_1_ENDFILTEE` = 0x00004000 ,  
`DF_1_DISPRELDNE` = 0x00008000 ,  
`DF_1_DISPRELPND` = 0x00010000 }

*State flags selectable in the Elf32\_Dyn.d\_un.d\_val / Elf64\_Dyn.d\_un.d\_val element of the DT\_FLAGS\_1 entry in the dynamic section.*

- enum `Elf_DTF_1s`

*Flags for the feature selection in DT\_FEATURE\_1.*

- enum `Elf_DF_P1s` { `DF_P1_LAZYLOAD` = 0x00000001 , `DF_P1_GROUPPERM` = 0x00000002 }

*Flags in the DT\_POSFLAG\_1 entry effecting only the next DT\_\* entry.*

- enum `Elf_R_386_s` {  
`R_386_NONE` = 0 , `R_386_32` = 1 , `R_386_PC32` = 2 , `R_386_GOT32` = 3 ,  
`R_386_PLT32` = 4 , `R_386_COPY` = 5 , `R_386_GLOB_DAT` = 6 , `R_386_JMP_SLOT` = 7 ,  
`R_386_RELATIVE` = 8 , `R_386_GOTOFF` = 9 , `R_386_GOTPC` = 10 , `R_386_32PLT` = 11 ,  
`R_386_TLS_TPOFF` = 14 , `R_386_TLS_IE` = 15 , `R_386_TLS_GOTIE` = 16 , `R_386_TLS_LE` = 17 ,  
`R_386_TLS_GD` = 18 , `R_386_TLS_LDM` = 19 , `R_386_16` = 20 , `R_386_PC16` = 21 ,  
`R_386_8` = 22 , `R_386_PC8` = 23 , `R_386_TLS_GD_32` = 24 , `R_386_TLS_GD_PUSH` = 25 ,  
`R_386_TLS_GD_CALL` = 26 , `R_386_TLS_GD_POP` = 27 , `R_386_TLS_LDM_32` = 28 , `R_386_TLS_LDM_PUSH`  
= 29 ,  
`R_386_TLS_LDM_CALL` = 30 , `R_386_TLS_LDM_POP` = 31 , `R_386_TLS_LDO_32` = 32 , `R_386_TLS_IE_32`  
= 33 ,  
`R_386_TLS_LE_32` = 34 , `R_386_TLS_DTPMOD32` = 35 , `R_386_TLS_DTPOFF32` = 36 , `R_386_TLS_TPOFF32`  
= 37 ,  
`R_386_NUM` = 38 }

*Relocation types (processor specific).*

- enum `Elf_EF_ARM_s` { }

*ARM specific declarations.*

- enum `Elf_STT_ARM_s`

*Additional symbol types for Thumb.*

- enum `Elf_SHF_s_ARM` { `SHF_ARM_ENTRYSECT` = 0x10000000 , `SHF_ARM_COMDEF` = 0x80000000 }

*ARM-specific values for Elf32\_Shdr.sh\_flags / Elf64\_Shdr.sh\_flags.*

- enum `Elf_ARM_SBs` { `PF_ARM_SB` = 0x10000000 }

*ARM-specific program header flags.*

- enum `Elf_R_ARM_s` {  
`R_ARM_NONE` = 0 , `R_ARM_PC24` = 1 , `R_ARM_ABS32` = 2 , `R_ARM_REL32` = 3 ,  
`R_ARM_PC13` = 4 , `R_ARM_ABS16` = 5 , `R_ARM_ABS12` = 6 , `R_ARM_THM_ABS5` = 7 ,  
`R_ARM_ABS8` = 8 , `R_ARM_SBREL32` = 9 , `R_ARM_THM_PC22` = 10 , `R_ARM_THM_PC8` = 11 ,  
`R_ARM_AMP_VCALL9` = 12 , `R_ARM_SWI24` = 13 , `R_ARM_THM_SWI8` = 14 , `R_ARM_XPC25` = 15 ,  
`R_ARM_THM_XPC22` = 16 , `R_ARM_COPY` = 20 , `R_ARM_GLOB_DAT` = 21 , `R_ARM_JUMP_SLOT` = 22 ,  
`R_ARM_RELATIVE` = 23 , `R_ARM_GOTOFF` = 24 , `R_ARM_GOTPC` = 25 , `R_ARM_GOT32` = 26 ,  
`R_ARM_PLT32` = 27 , `R_ARM_ALU_PCREL_7_0` = 32 , `R_ARM_ALU_PCREL_15_8` = 33 , `R_ARM_↵`  
`ALU_PCREL_23_15` = 34 ,  
`R_ARM_LDR_SBREL_11_0` = 35 , `R_ARM_ALU_SBREL_19_12` = 36 , `R_ARM_ALU_SBREL_27_20` =  
37 , `R_ARM_GNU_VTENTRY` = 100 ,  
`R_ARM_GNU_VTINHERIT` = 101 , `R_ARM_THM_PC11` = 102 , `R_ARM_THM_PC9` = 103 , `R_ARM_↵`  
`RXPC25` = 249 ,  
`R_ARM_RSBREL32` = 250 , `R_ARM_THM_RPC22` = 251 , `R_ARM_RREL32` = 252 , `R_ARM_RABS22` =  
253 ,  
`R_ARM_RPC24` = 254 , `R_ARM_RBASE` = 255 , `R_ARM_NUM` = 256 }

*ARM relocations.*

- enum [Elf\\_R\\_AARCH64\\_s](#) { [R\\_AARCH64\\_NONE](#) = 0 , [R\\_AARCH64\\_RELATIVE](#) = 1027 }

*AARCH64 relocations.*

- enum [Elf\\_R\\_X86\\_64\\_s](#) {  
[R\\_X86\\_64\\_NONE](#) = 0 , [R\\_X86\\_64\\_64](#) = 1 , [R\\_X86\\_64\\_PC32](#) = 2 , [R\\_X86\\_64\\_GOT32](#) = 3 ,  
[R\\_X86\\_64\\_PLT32](#) = 4 , [R\\_X86\\_64\\_COPY](#) = 5 , [R\\_X86\\_64\\_GLOB\\_DAT](#) = 6 , [R\\_X86\\_64\\_JUMP\\_SLOT](#) = 7 ,  
[R\\_X86\\_64\\_RELATIVE](#) = 8 , [R\\_X86\\_64\\_GOTPCREL](#) = 9 , [R\\_X86\\_64\\_32](#) = 10 , [R\\_X86\\_64\\_32S](#) = 11 ,  
[R\\_X86\\_64\\_16](#) = 12 , [R\\_X86\\_64\\_PC16](#) = 13 , [R\\_X86\\_64\\_8](#) = 14 , [R\\_X86\\_64\\_PC8](#) = 15 ,  
[R\\_X86\\_64\\_DTPMOD64](#) = 16 , [R\\_X86\\_64\\_DTPOFF64](#) = 17 , [R\\_X86\\_64\\_TPOFF64](#) = 18 , [R\\_X86\\_64\\_TLSGD](#)  
= 19 ,  
[R\\_X86\\_64\\_TLSLD](#) = 20 , [R\\_X86\\_64\\_DTPOFF32](#) = 21 , [R\\_X86\\_64\\_GOTTPOFF](#) = 22 , [R\\_X86\\_64\\_TPOFF32](#)  
= 23 ,  
[R\\_X86\\_64\\_NUM](#) = 24 }

*AMD x86-64 relocations.*

- enum [Elf\\_STNs](#)  
*Symbol Table Entry.*
- enum [Elf\\_STBs](#) {  
[STB\\_LOCAL](#) = 0 , [STB\\_GLOBAL](#) = 1 , [STB\\_WEAK](#) = 2 , [STB\\_LOOS](#) = 10 ,  
[STB\\_HIOS](#) = 12 , [STB\\_LOPROC](#) = 13 , [STB\\_HIPROC](#) = 15 }

*Symbol Binding.*

- enum [Elf\\_STTs](#) {  
[STT\\_NOTYPE](#) = 0 , [STT\\_OBJECT](#) = 1 , [STT\\_FUNC](#) = 2 , [STT\\_SECTION](#) = 3 ,  
[STT\\_FILE](#) = 4 , [STT\\_LOOS](#) = 10 , [STT\\_HIOS](#) = 12 , [STT\\_LOPROC](#) = 13 ,  
[STT\\_HIPROC](#) = 15 }

*Symbol Types.*

- enum [Elf\\_ATs](#) {  
[AT\\_NULL](#) = 0 , [AT\\_IGNORE](#) = 1 , [AT\\_EXECFD](#) = 2 , [AT\\_PHDR](#) = 3 ,  
[AT\\_PHENT](#) = 4 , [AT\\_PHNUM](#) = 5 , [AT\\_PAGESZ](#) = 6 , [AT\\_BASE](#) = 7 ,  
[AT\\_FLAGS](#) = 8 , [AT\\_ENTRY](#) = 9 , [AT\\_NOTELF](#) = 10 , [AT\\_UID](#) = 11 ,  
[AT\\_EUID](#) = 12 , [AT\\_GID](#) = 13 , [AT\\_EGID](#) = 14 , [AT\\_L4\\_AUX](#) = 0xf0 ,  
[AT\\_L4\\_ENV](#) = 0xf1 , [AT\\_L4\\_KIP](#) = 0xf2 }

*Legal values for [Elf32\\_Auxv.atype](#) / [Elf64\\_Auxv.atype](#).*

## ELF types

- typedef [l4\\_uint32\\_t](#) [Elf32\\_Addr](#)  
*size 4 align 4*
- typedef [l4\\_uint32\\_t](#) [Elf32\\_Off](#)  
*size 4 align 4*
- typedef [l4\\_uint16\\_t](#) [Elf32\\_Half](#)  
*size 2 align 2*
- typedef [l4\\_uint32\\_t](#) [Elf32\\_Word](#)  
*size 4 align 4*
- typedef [l4\\_int32\\_t](#) [Elf32\\_Sword](#)  
*size 4 align 4*
- typedef [l4\\_uint64\\_t](#) [Elf64\\_Addr](#)  
*size 8 align 8*
- typedef [l4\\_uint64\\_t](#) [Elf64\\_Off](#)  
*size 8 align 8*
- typedef [l4\\_uint16\\_t](#) [Elf64\\_Half](#)  
*size 2 align 2*
- typedef [l4\\_uint32\\_t](#) [Elf64\\_Word](#)  
*size 4 align 4*

- typedef [l4\\_int32\\_t](#) Elf64\_Sword  
*size 4 align 4*
- typedef [l4\\_uint64\\_t](#) Elf64\_Xword  
*size 8 align 8*
- typedef [l4\\_int64\\_t](#) Elf64\_Sxword  
*size 8 align 8*

### 13.16.9.1 Detailed Description

Functions and types related to ELF binaries.

### 13.16.9.2 Macro Definition Documentation

#### 13.16.9.2.1 ELF32\_R\_TYPE

```
#define ELF32_R_TYPE(  
    i)
```

**Value:**

```
((unsigned char)(i))
```

**See also**

[Elf\\_R\\_386s](#).

Definition at line [663](#) of file [elf.h](#).

#### 13.16.9.2.2 ELF32\_ST\_BIND

```
#define ELF32_ST_BIND(  
    i)
```

**Value:**

```
((i) >> 4)
```

**See also**

[Elf\\_STBs](#).

Definition at line [893](#) of file [elf.h](#).

#### 13.16.9.2.3 ELF32\_ST\_TYPE

```
#define ELF32_ST_TYPE(  
    i)
```

**Value:**

```
((i) & 0xf)
```

**See also**

[Elf\\_STTs](#).

Definition at line [896](#) of file [elf.h](#).

#### 13.16.9.2.4 ELF64\_R\_TYPE

```
#define ELF64_R_TYPE(  
    i)
```

**Value:**

```
((i) & 0xffffffffL)
```

**See also**

[Elf\\_R\\_386s](#).

Definition at line [671](#) of file [elf.h](#).

#### 13.16.9.2.5 ELF64\_ST\_BIND

```
#define ELF64_ST_BIND(  
    i)
```

**Value:**

```
((i) >> 4)
```

**See also**

[Elf\\_STBs](#)

Definition at line [902](#) of file [elf.h](#).

#### 13.16.9.2.6 ELF64\_ST\_TYPE

```
#define ELF64_ST_TYPE(  
    i)
```

**Value:**

```
((i) & 0xf)
```

**See also**

[Elf\\_STTs](#)

Definition at line [905](#) of file [elf.h](#).



### 13.16.9.3 Enumeration Type Documentation

#### 13.16.9.3.1 anonymous enum

anonymous enum

##### Enumerator

EI_NIDENT	Number of characters.
-----------	-----------------------

Definition at line 117 of file [elf.h](#).

#### 13.16.9.3.2 Elf\_ARM\_SBs

enum [Elf\\_ARM\\_SBs](#)

ARM-specific program header flags.

##### Enumerator

PF_ARM_SB	Segment contains the location addressed by the static base.
-----------	---

Definition at line 770 of file [elf.h](#).

#### 13.16.9.3.3 Elf\_ATs

enum [Elf\\_ATs](#)

Legal values for [Elf32\\_Auxv.atype](#) / [Elf64\\_Auxv.atype](#).

##### Enumerator

AT_NULL	End of vector.
AT_IGNORE	Entry should be ignored.
AT_EXECD	File descriptor of program.
AT_PHDR	Program headers for program.
AT_PHEM	Size of program header entry.
AT_PHNUM	Number of program headers.
AT_PAGESZ	System page size.
AT_BASE	Base address of interpreter.
AT_FLAGS	Flags.
AT_ENTRY	Entry point of program.
AT_NOTELF	Program is not ELF.
AT_UID	Real UID.

AT_EUID	Effective UID.
AT_GID	Real GID.
AT_EGID	Effective GID.
AT_L4_AUX	<a href="#">L4Re</a> AUX section.
AT_L4_ENV	<a href="#">L4Re</a> ENV section.
AT_L4_KIP	<a href="#">L4Re</a> KIP section.

Definition at line [939](#) of file [elf.h](#).

#### 13.16.9.3.4 Elf\_CLASSES

enum [Elf\\_CLASSES](#)

File class or capacity.

##### Enumerator

ELFCLASSNONE	Invalid class.
ELFCLASS32	32-bit object
ELFCLASS64	64-bit object
ELFCLASSNUM	Mask for 32-bit or 64-bit class.

Definition at line [298](#) of file [elf.h](#).

#### 13.16.9.3.5 Elf\_DATAs

enum [Elf\\_DATAs](#)

Data encoding.

##### Enumerator

ELFDATANONE	invalid data encoding
ELFDATA2LSB	0x01020304 => [ 0x04 0x03 0x02 0x01 ]
ELFDATA2MSB	0x01020304 => [ 0x01 0x02 0x03 0x04 ]
ELFDATANUM	Mask for valid data encoding.

Definition at line [307](#) of file [elf.h](#).

**13.16.9.3.6 Elf\_DF\_1s**

enum [Elf\\_DF\\_1s](#)

State flags selectable in the Elf32\_Dyn.d\_un.d\_val / Elf64\_Dyn.d\_un.d\_val element of the DT\_FLAGS\_1 entry in the dynamic section.

**Enumerator**

DF_1_NOW	Set RTLD_NOW for this object.
DF_1_GLOBAL	Set RTLD_GLOBAL for this object.
DF_1_GROUP	Set RTLD_GROUP for this object.
DF_1_NODELETE	Set RTLD_NODELETE for this object.
DF_1_LOADFLTR	Trigger filtee loading at runtime.
DF_1_INITFIRST	Set RTLD_INITFIRST for this object.
DF_1_NOOPEN	Set RTLD_NOOPEN for this object.
DF_1_ORIGIN	\$ORIGIN must be handled.
DF_1_DIRECT	Direct binding enabled.
DF_1_INTERPOSE	Object is used to interpose.
DF_1_NODEFLIB	Ignore default lib search path.
DF_1_NODUMP	Object can't be dldump'ed.
DF_1_CONFALT	Configuration alternative created.
DF_1_ENDFILTEE	Filtee terminates filters search.
DF_1_DISPRELDNE	Disp reloc applied at build time.
DF_1_DISPRELPND	Disp reloc applied at run-time.

Definition at line [594](#) of file [elf.h](#).

**13.16.9.3.7 Elf\_DF\_P1s**

enum [Elf\\_DF\\_P1s](#)

Flags in the DT\_POSFLAG\_1 entry effecting only the next DT\_\* entry.

**Enumerator**

DF_P1_LAZYLOAD	Lazyload following object.
DF_P1_GROUPPERM	Symbols from next object are not generally available.

Definition at line [623](#) of file [elf.h](#).

### 13.16.9.3.8 Elf\_DFs

enum [Elf\\_DFs](#)

Values of Elf32\_Dyn.d\_un.d\_val, Elf64\_Dyn.d\_un.d\_val in the DT\_FLAGS entry.

#### Enumerator

DF_ORIGIN	Object may use DF_ORIGIN.
DF_SYMBOLIC	Symbol resolutions starts here.
DF_TEXTREL	Object contains text relocations.
DF_BIND_NOW	No lazy binding for this object.
DF_STATIC_TLS	Module uses the static TLS model.

Definition at line [581](#) of file [elf.h](#).

### 13.16.9.3.9 Elf\_DTs

enum [Elf\\_DTs](#)

Dynamic Array Tags.

See also

[Elf32\\_Dyn.d\\_tag](#), [Elf64\\_Dyn.d\\_tag](#).

#### Enumerator

DT_NULL	end of _DYNAMIC array
DT_NEEDED	name of a needed library
DT_PLTRELSZ	total size of relocation entry
DT_PLTGOT	address assoc with prog link table
DT_HASH	address of symbol hash table
DT_STRTAB	address of string table
DT_SYMTAB	address of symbol table
DT_RELA	address of relocation table
DT_RELASZ	total size of relocation table
DT_RELAENT	size of DT_RELA relocation entry
DT_STRSZ	size of the string table
DT_SYMENT	size of a symbol table entry
DT_INIT	address of initialization function
DT_FINI	address of termination function
DT_SONAME	name of the shared object
DT_RPATH	search library path
DT_SYMBOLIC	alter symbol resolution algorithm

DT_REL	address of relocation table
DT_RELSZ	total size of DT_REL relocation table
DT_RELENT	size of the DT_REL relocation entry
DT_PTRREL	type of relocation entry
DT_DEBUG	for debugging purposes
DT_TEXTREL	at least on entry changes r/o section
DT_JMPREL	address of relocation entries
DT_BIND_NOW	Process relocations of object.
DT_INIT_ARRAY	Array with addresses of init fct.
DT_FINI_ARRAY	Array with addresses of fini fct.
DT_INIT_ARRAYSZ	Size in bytes of DT_INIT_ARRAY.
DT_FINI_ARRAYSZ	Size in bytes of DT_FINI_ARRAY.
DT_RUNPATH	Library search path.
DT_FLAGS	Flags for the object being loaded.
DT_ENCODING	Start of encoded range.
DT_PREINIT_ARRAY	Array with addresses of preinit fct.
DT_PREINIT_ARRAYSZ	size in bytes of DT_PREINIT_ARRAY
DT_NUM	Number used.
DT_LOOS	Start of OS-specific.
DT_HIOS	End of OS-specific.
DT_LOPROC	processor-specific
DT_HIPROC	processor-specific

Definition at line 535 of file [elf.h](#).

#### 13.16.9.3.10 Elf\_EF\_ARM\_s

enum [Elf\\_EF\\_ARM\\_s](#)

ARM specific declarations.

Processor specific flags for the ELF header e\_flags field.

##### Enumerator

EF_ARM_ALIGN8	8-bit structure alignment is in use
---------------	-------------------------------------

Definition at line 730 of file [elf.h](#).

#### 13.16.9.3.11 Elf\_EIs

enum [Elf\\_EIs](#)

Identification Indices.

See also

[Elf32\\_Ehdr.e\\_ident](#), [Elf64\\_Ehdr.e\\_ident](#)

### Enumerator

EI_MAG0	file id 0
EI_MAG1	file id 1
EI_MAG2	file id 2
EI_MAG3	file id 3
EI_CLASS	file class
EI_DATA	data encoding
EI_VERSION	file version
EI_OSABI	Operating system / ABI identification.
EI_ABIVERSION	ABI version.
EI_PAD	start of padding bytes

Definition at line 274 of file [elf.h](#).

### 13.16.9.3.12 Elf\_EMs

enum [Elf\\_EMs](#)

Required architecture.

See also

[Elf32\\_Ehdr.e\\_machine](#), [Elf64\\_Ehdr.e\\_machine](#)

### Enumerator

EM_NONE	no machine
EM_M32	AT&T WE 32100.
EM_SPARC	SPARC.
EM_386	Intel 80386.
EM_68K	Motorola 68000.
EM_88K	Motorola 88000.
EM_860	Intel 80860.
EM_MIPS	MIPS RS3000 big-endian.
EM_MIPS_RS4_BE	MIPS RS4000 big-endian.
EM_SPARC64	SPARC 64-bit.
EM_PARISC	HP PA-RISC.
EM_VPP500	Fujitsu VPP500.
EM_SPARC32PLUS	Sun's V8plus.
EM_960	Intel 80960.

EM_PPC	PowerPC.
EM_V800	NEC V800.
EM_FR20	Fujitsu FR20.
EM_RH32	TRW RH-32.
EM_RCE	Motorola RCE.
EM_ARM	Advanced RISC Machines ARM.
EM_ALPHA	Digital Alpha.
EM_SH	Hitachi SuperH.
EM_SPARCV9	SPARC v9 64-bit.
EM_TRICORE	Siemens Tricore embedded processor.
EM_ARC	Argonaut RISC Core, Argonaut Techn Inc.
EM_H8_300	Hitachi H8/300.
EM_H8_300H	Hitachi H8/300H.
EM_H8S	Hitachi H8/S.
EM_H8_500	Hitachi H8/500.
EM_IA_64	HP/Intel IA-64.
EM_MIPS_X	Stanford MIPS-X.
EM_COLDFIRE	Motorola Coldfire.
EM_68HC12	Motorola M68HC12.
EM_X86_64	Advanced Micro Devices x86-64.
EM_PDSP	Sony DSP Processor.
EM_FX66	Siemens FX66 microcontroller.
EM_ST9PLUS	STMicroelectronics ST9+ 8/16 mc.
EM_ST7	STmicroelectronics ST7 8 bit mc.
EM_68HC16	Motorola MC68HC16 microcontroller.
EM_68HC11	Motorola MC68HC11 microcontroller.
EM_68HC08	Motorola MC68HC08 microcontroller.
EM_68HC05	Motorola MC68HC05 microcontroller.
EM_SVX	Silicon Graphics SVx.
EM_ST19	STMicroelectronics ST19 8 bit mc.
EM_VAX	Digital VAX.
EM_CRIS	Axis Communications 32-bit embedded processor.
EM_JAVELIN	Infineon Technologies 32-bit embedded processor.
EM_FIREPATH	Element 14 64-bit DSP Processor.
EM_ZSP	LSI Logic 16-bit DSP Processor.
EM_MMIX	Donald Knuth's educational 64-bit processor.
EM_HUANY	Harvard University machine-independent object files.
EM_PRISM	SiTera Prism.
EM_AVR	Atmel AVR 8-bit microcontroller.
EM_FR30	Fujitsu FR30.
EM_D10V	Mitsubishi D10V.
EM_D30V	Mitsubishi D30V.

EM_V850	NEC v850.
EM_M32R	Mitsubishi M32R.
EM_MN10300	Matsushita MN10300.
EM_MN10200	Matsushita MN10200.
EM_PJ	picoJava
EM_OPENRISC	OpenRISC 32-bit embedded processor.
EM_ARC_A5	ARC Cores Tangent-A5.
EM_XTENSA	Tensilica Xtensa Architecture.
EM_ALTERA_NIOS2	Altera Nios II.
EM_AARCH64	ARM AARCH64.
EM_TILEPRO	Tilera TILEPro.
EM_MICROBLAZE	Xilinx MicroBlaze.
EM_TILEGX	Tilera TILE-Gx.
EM_RISCV	RISC-V.

Definition at line 183 of file [elf.h](#).

#### 13.16.9.3.13 Elf\_ETs

enum [Elf\\_ETs](#)

Object file type.

See also

[Elf32\\_Ehdr.e\\_type](#), [Elf64\\_Ehdr.e\\_type](#)

#### Enumerator

ET_NONE	no file type
ET_REL	relocatable file
ET_EXEC	executable file
ET_DYN	shared object file
ET_CORE	core file
ET_LOPROC	processor-specific
ET_HIPROC	processor-specific

Definition at line 168 of file [elf.h](#).

#### 13.16.9.3.14 Elf\_EVs

enum [Elf\\_EVs](#)

Object file version.



See also

[Elf32\\_Ehdr.e\\_version](#), [Elf64\\_Ehdr.e\\_version](#)

#### Enumerator

EV_NONE	Invalid version.
EV_CURRENT	Current version.

Definition at line 266 of file [elf.h](#).

#### 13.16.9.3.15 Elf\_MAGs

enum [Elf\\_MAGs](#)

Magic number.

#### Enumerator

ELFMAG0	e_ident[EI_MAG0]
ELFMAG1	e_ident[EI_MAG1]
ELFMAG2	e_ident[EI_MAG2]
ELFMAG3	e_ident[EI_MAG3]

Definition at line 289 of file [elf.h](#).

#### 13.16.9.3.16 Elf\_NT\_s\_core

enum [Elf\\_NT\\_s\\_core](#)

Legal values for note segment descriptor types for core files.

#### Enumerator

NT_PRSTATUS	Contains copy of prstatus struct.
NT_FPREGSET	Contains copy of fpregset struct.
NT_PRPSINFO	Contains copy of prpsinfo struct.
NT_PRXREG	Contains copy of prxregset struct.
NT_TASKSTRUCT	Contains copy of task structure.
NT_PLATFORM	String from sysinfo(SI_PLATFORM).
NT_AUXV	Contains copy of auxv array.
NT_GWINDOWS	Contains copy of gwindows struct.
NT_ASRS	Contains copy of asrset struct.
NT_PSTATUS	Contains copy of pstatus struct.
NT_PSINFO	Contains copy of psinfo struct.

NT_PRCRED	Contains copy of prcred struct.
NT_UTSNAME	Contains copy of utsname struct.
NT_LWPSTATUS	Contains copy of lwpstatus struct.
NT_LWPSINFO	Contains copy of lwpinfo struct.
NT_PRFPXREG	Contains copy of fprxregset struct.

Definition at line 486 of file [elf.h](#).

### 13.16.9.3.17 Elf\_NTs\_obj

enum [Elf\\_NTs\\_obj](#)

Legal values for the note segment descriptor types for object files.

#### Enumerator

NT_VERSION	Contains a version string.
------------	----------------------------

Definition at line 507 of file [elf.h](#).

### 13.16.9.3.18 Elf\_OSABIs

enum [Elf\\_OSABIs](#)

Identify operating system and ABI to which the object is targeted.

#### Enumerator

ELFOSABI_NONE	UNIX System V ABI.
ELFOSABI_SYSV	Alias.
ELFOSABI_HPUX	HP-UX.
ELFOSABI_NETBSD	NetBSD.
ELFOSABI_LINUX	Linux.
ELFOSABI_SOLARIS	Sun Solaris.
ELFOSABI_AIX	IBM AIX.
ELFOSABI_IRIX	SGI Irix.
ELFOSABI_FREEBSD	FreeBSD.
ELFOSABI_TRU64	Compaq TRU64 UNIX.
ELFOSABI_MODESTO	Novell Modesto.
ELFOSABI_OPENBSD	OpenBSD.
ELFOSABI_ARM	ARM.
ELFOSABI_STANDALONE	Standalone (embedded) application.

Definition at line 316 of file [elf.h](#).

### 13.16.9.3.19 ELF\_PFs

enum [ELF\\_PFs](#)

Segment permissions.

#### Enumerator

PF_X	Executable.
PF_W	Write.
PF_R	Read.
PF_MASKOS	OS-specific.
PF_MASKPROC	Processor-specific.

Definition at line [476](#) of file [elf.h](#).

### 13.16.9.3.20 Elf\_PTs

enum [Elf\\_PTs](#)

Segment types.

#### Enumerator

PT_NULL	array is unused
PT_LOAD	loadable
PT_DYNAMIC	dynamic linking information
PT_INTERP	path to interpreter
PT_NOTE	auxiliary information
PT_SHLIB	reserved
PT_PHDR	location of the pht itself
PT_TLS	Thread-local storage segment.
PT_NUM	Number of defined types.
PT_LOOS	OS-specific.
PT_HIOS	OS-specific.
PT_LOPROC	processor-specific
PT_HIPROC	processor-specific
PT_GNU_EH_FRAME	EH frame information.
PT_GNU_STACK	Flags for stack.
PT_GNU_RELRO	Read only after reloc.
PT_L4_STACK	Address of the stack.
PT_L4_AUX	Address of the AUX structures.

Definition at line [451](#) of file [elf.h](#).

**13.16.9.3.21 Elf\_R\_386\_s**enum [Elf\\_R\\_386\\_s](#)

Relocation types (processor specific).

**Enumerator**

R_386_NONE	none
R_386_32	S + A.
R_386_PC32	S + A - P.
R_386_GOT32	G + A - P.
R_386_PLT32	L + A - P.
R_386_COPY	none
R_386_GLOB_DAT	S.
R_386_JMP_SLOT	S.
R_386_RELATIVE	B + A.
R_386_GOTOFF	S + A - GOT.
R_386_GOTPC	GOT + A - P.
R_386_TLS_TPOFF	Offset in static TLS block.
R_386_TLS_IE	Address of GOT entry for static TLS block offset.
R_386_TLS_GOTIE	GOT entry for static TLS block offset.
R_386_TLS_LE	Offset relative to static TLS block.
R_386_TLS_GD	Direct 32 bit for GNU version of general dynamic thread local data.
R_386_TLS_LDM	Direct 32 bit for GNU version of local dynamic thread local data in LE code.
R_386_TLS_GD_32	Direct 32 bit for general dynamic thread local data.
R_386_TLS_GD_PUSH	Tag for pushl in GD TLS code.
R_386_TLS_GD_CALL	Relocation for call to <code>__tls_get_addr()</code> .
R_386_TLS_GD_POP	Tag for popl in GD TLS code.
R_386_TLS_LDM_32	Direct 32 bit for local dynamic thread local data in LE code.
R_386_TLS_LDM_PUSH	Tag for pushl in LDM TLS code.
R_386_TLS_LDM_CALL	Relocation for call to <code>__tls_get_addr()</code> in LDM code.
R_386_TLS_LDM_POP	Tag for popl in LDM TLS code.
R_386_TLS_LDO_32	Offset relative to TLS block.
R_386_TLS_IE_32	GOT entry for negated static TLS block offset.
R_386_TLS_LE_32	Negated offset relative to static TLS block.
R_386_TLS_DTPMOD32	ID of module containing symbol.
R_386_TLS_DTPOFF32	Offset in TLS block.
R_386_TLS_TPOFF32	Negated offset in static TLS block.
R_386_NUM	Keep this the last entry.

Definition at line [677](#) of file [elf.h](#).

**13.16.9.3.22 Elf\_R\_AARCH64\_s**

enum [Elf\\_R\\_AARCH64\\_s](#)

AARCH64 relocations.

**Enumerator**

R_AARCH64_NONE	No reloc.
----------------	-----------

Definition at line [825](#) of file [elf.h](#).

**13.16.9.3.23 Elf\_R\_ARM\_s**

enum [Elf\\_R\\_ARM\\_s](#)

ARM relocations.

**Enumerator**

R_ARM_NONE	No reloc.
R_ARM_PC24	PC relative 26 bit branch.
R_ARM_ABS32	Direct 32 bit.
R_ARM_REL32	PC relative 32 bit.
R_ARM_ABS16	Direct 16 bit.
R_ARM_ABS12	Direct 12 bit.
R_ARM_ABS8	Direct 8 bit.
R_ARM_COPY	Copy symbol at runtime.
R_ARM_GLOB_DAT	Create GOT entry.
R_ARM_JUMP_SLOT	Create PLT entry.
R_ARM_RELATIVE	Adjust by program base.
R_ARM_GOTOFF	32 bit offset to GOT
R_ARM_GOTPC	32 bit PC relative offset to GOT
R_ARM_GOT32	32 bit GOT entry
R_ARM_PLT32	32 bit PLT address
R_ARM_THM_PC11	thumb unconditional branch
R_ARM_THM_PC9	thumb conditional branch
R_ARM_NUM	Keep this the last entry.

Definition at line [777](#) of file [elf.h](#).

**13.16.9.3.24 Elf\_R\_X86\_64\_s**

enum [Elf\\_R\\_X86\\_64\\_s](#)

AMD x86-64 relocations.

**Enumerator**

R_X86_64_NONE	No reloc.
R_X86_64_64	Direct 64 bit.
R_X86_64_PC32	PC relative 32 bit signed.
R_X86_64_GOT32	32 bit GOT entry
R_X86_64_PLT32	32 bit PLT address
R_X86_64_COPY	Copy symbol at runtime.
R_X86_64_GLOB_DAT	Create GOT entry.
R_X86_64_JUMP_SLOT	Create PLT entry.
R_X86_64_RELATIVE	Adjust by program base.
R_X86_64_GOTPCREL	32 bit signed PC relative offset to GOT
R_X86_64_32	Direct 32 bit zero extended.
R_X86_64_32S	Direct 32 bit sign extended.
R_X86_64_16	Direct 16 bit zero extended.
R_X86_64_PC16	16 bit sign extended pc relative
R_X86_64_8	Direct 8 bit sign extended.
R_X86_64_PC8	8 bit sign extended pc relative
R_X86_64_DTPOFF64	ID of module containing symbol.
R_X86_64_DTPOFF64	Offset in module's TLS block.
R_X86_64_TPOFF64	Offset in initial TLS block.
R_X86_64_TLSGD	32 bit signed PC relative offset to two GOT entries for GD symbol
R_X86_64_TLSLD	32 bit signed PC relative offset to two GOT entries for LD symbol
R_X86_64_DTPOFF32	Offset in TLS block.
R_X86_64_GOTTPOFF	32 bit signed PC relative offset to GOT entry for IE symbol
R_X86_64_TPOFF32	Offset in initial TLS block.

Definition at line [832](#) of file [elf.h](#).

**13.16.9.3.25 Elf\_SHF\_s\_ARM**

enum [Elf\\_SHF\\_s\\_ARM](#)

ARM-specific values for [Elf32\\_Shdr.sh\\_flags](#) / [Elf64\\_Shdr.sh\\_flags](#).

**Enumerator**

SHF_ARM_ENTRYSECT	Section contains an entry point.
-------------------	----------------------------------

SHF_ARM_COMDEF	Section may be multiply defined in the input to a link step.
----------------	--

Definition at line 762 of file [elf.h](#).

### 13.16.9.3.26 Elf\_SHFs

enum [Elf\\_SHFs](#)

Section attribute flags.

#### Enumerator

SHF_WRITE	writeable during execution
SHF_ALLOC	section occupies virt memory
SHF_EXECINSTR	code section
SHF_MERGE	Might be merged.
SHF_STRINGS	Contains nul-terminated strings.
SHF_INFO_LINK	'sh_info' contains SHT index
SHF_LINK_ORDER	Preserve order after combining.
SHF_OS_NONCONFORMING	Non-standard OS-specific handling required.
SHF_GROUP	Section is member of a group.
SHF_TLS	Section hold thread-local data.
SHF_MASKOS	OS-specific.
SHF_MASKPROC	processor-specific mask

Definition at line 406 of file [elf.h](#).

### 13.16.9.3.27 Elf\_SHNs

enum [Elf\\_SHNs](#)

Special section indexes.

#### Enumerator

SHN_UNDEF	undefined section header entry
SHN_LORESERVE	lower bound of reserved indexes
SHN_LOPROC	lower bound of proc spec entr
SHN_HIPROC	upper bound of proc spec entr
SHN_ABS	absolute values for ref
SHN_COMMON	common symbols
SHN_HIRESERVE	upper bound of reserved indexes

Definition at line 335 of file [elf.h](#).

### 13.16.9.3.28 Elf\_SHTs

enum [Elf\\_SHTs](#)

Section type.

#### Enumerator

SHT_NULL	inactive section header
SHT_PROGBITS	information defined by program
SHT_SYMTAB	symbol table
SHT_STRTAB	string table
SHT_RELA	reloc entries w/ explicit addends
SHT_HASH	symbol hash table
SHT_DYNAMIC	information for dynamic linking
SHT_NOTE	information that marks the file
SHT_NOBITS	occupies no space in the file
SHT_REL	reloc entries w/o explicit addends
SHT_SHLIB	reserved + unspecified semantics
SHT_DYNSYM	symbol table (dynamic
SHT_INIT_ARRAY	Array of constructors.
SHT_FINI_ARRAY	Array of destructors.
SHT_PREINIT_ARRAY	Array of pre-constructors.
SHT_GROUP	Section group.
SHT_SYMTAB_SHNDX	Extended section indices.
SHT_NUM	Number of defined types.
SHT_LOOS	Start OS-specific.
SHT_HIOS	End OS-specific.
SHT_LOPROC	Start processor-specific.
SHT_HIPROC	End processor-specific.
SHT_LOUSER	Start application-specific.
SHT_HIUSER	End application-specific.

Definition at line [377](#) of file [elf.h](#).

### 13.16.9.3.29 Elf\_STBs

enum [Elf\\_STBs](#)

Symbol Binding.



See also

[ELF32\\_ST\\_BIND](#), [ELF64\\_ST\\_BIND](#)

#### Enumerator

STB_LOCAL	not visible outside object file
STB_GLOBAL	visible to all objects being combined
STB_WEAK	resemble global symbols
STB_LOOS	OS-specific.
STB_HIOS	OS-specific.
STB_LOPROC	Processor-specific.
STB_HIPROC	Processor-specific.

Definition at line 912 of file [elf.h](#).

#### 13.16.9.3.30 Elf\_STTs

enum [Elf\\_STTs](#)

Symbol Types.

See also

[ELF32\\_ST\\_TYPE](#), [ELF64\\_ST\\_TYPE](#)

#### Enumerator

STT_NOTYPE	symbol's type not specified
STT_OBJECT	associated with a data object
STT_FUNC	associated with a function or other code
STT_SECTION	associated with a section
STT_FILE	source file name associated with object
STT_LOOS	OS-specific.
STT_HIOS	OS-specific.
STT_LOPROC	processor-specific
STT_HIPROC	processor-specific

Definition at line 925 of file [elf.h](#).

### 13.16.10 Kernel Interface Page API

Collaboration diagram for Kernel Interface Page API:



#### Files

- file [kip.h](#)

#### Macros

- `#define l4util_kip_for_each_feature(s)`  
*Cycle through kernel features given in the KIP.*

#### Functions

- `L4_BEGIN_DECLS int l4util_kip_kernel_has_feature (l4_kernel_info_t const *k, char const *str)`  
*Check if kernel supports a feature.*
- `unsigned long l4util_kip_kernel_abi_version (l4_kernel_info_t const *k)`  
*Return kernel ABI version.*

#### 13.16.10.1 Detailed Description

#### 13.16.10.2 Macro Definition Documentation

##### 13.16.10.2.1 l4util\_kip\_for\_each\_feature

```
#define l4util_kip_for_each_feature(
    s)
```

#### Value:

`l4_kip_for_each_feature(s)`

Cycle through kernel features given in the KIP.

Cycles through all KIP kernel feature strings. `s` must be a character pointer (`char const *`) initialized with `l4_kip_version_string()`.

**Deprecated** Use `l4_kip_for_each_feature()`.

Definition at line 58 of file [kip.h](#).

### 13.16.10.3 Function Documentation

#### 13.16.10.3.1 l4util\_kip\_kernel\_abi\_version()

```
unsigned long l4util_kip_kernel_abi_version (  
    l4_kernel_info_t const * k)
```

Return kernel ABI version.

##### Parameters

<i>k</i>	Pointer to the kernel info page (KIP).
----------	--

##### Returns

Kernel ABI version.

References [L4\\_CV](#), and [L4\\_END\\_DECLS](#).

#### 13.16.10.3.2 l4util\_kip\_kernel\_has\_feature()

```
L4_BEGIN_DECLS int l4util_kip_kernel_has_feature (  
    l4_kernel_info_t const * k,  
    char const * str)
```

Check if kernel supports a feature.

##### Parameters

<i>k</i>	Pointer to the kernel info page (KIP).
<i>str</i>	Feature name to check.

##### Returns

1 if the kernel supports the feature, 0 if not.


Checks the feature field in the KIP for the given string.

**Deprecated** Use [l4\\_kip\\_kernel\\_has\\_feature\(\)](#).

References [L4\\_CV](#).

### 13.16.11 Comfortable Command Line Parsing

Collaboration diagram for Comfortable Command Line Parsing:



#### Typedefs

- typedef void(\* **parse\_cmd\_fn\_t**) (int)  
*Function type for PARSE\_CMD\_FN.*
- typedef void(\* **parse\_cmd\_fn\_arg\_t**) (int, const char \*, int)  
*Function type for PARSE\_CMD\_FN\_ARG.*

#### Enumerations

- enum [parse\\_cmd\\_type](#)  
*Types for parsing.*

#### Functions

- [L4\\_BEGIN\\_DECLS](#) int [parse\\_cmdline](#) (int \*argc, const char \*\*\*argv, int arg0,...)  
*Parse the command-line for specified arguments and store the values into variables.*

#### 13.16.11.1 Detailed Description

#### 13.16.11.2 Function Documentation

##### 13.16.11.2.1 [parse\\_cmdline\(\)](#)

```

L4_BEGIN_DECLS int parse_cmdline (
    int * argc,
    const char *** argv,
    int arg0,
    ...)
  
```

Parse the command-line for specified arguments and store the values into variables.

This Functions gets the command-line, and a list of command-descriptors. Then, the command-line is parsed according to the given descriptors, storing strings, switches and numeric arguments at given addresses, and possibly calling specified functions. A default help descriptor is added. Its purpose is to present a short command overview in the case the given command-line does not fit to the descriptors.

Each command-descriptor has the following form:

*short option char, long option name, comment, type, val, addr.*

The *short option char* specifies the short form of the described option. The short form will be recognized after a single dash, or in a group of short options preceeded by a single dash. Specify '' if no short form should be used.

The *long option name* specifies the long form of the described option. The long form will be recognized after two dashes. Specify 0 if no long form should be used for this option.

The *comment* is a string that will be used when presenting the short command-line help.

The *type* specifies, if the option should be recognized as

- a number (PARSE\_CMD\_INT),
- a switch (PARSE\_CMD\_SWITCH),
- a string (PARSE\_CMD\_STRING),
- a function call (PARSE\_CMD\_FN, PARSE\_CMD\_FN\_ARG),
- an increment/decrement operator (PARSE\_CMD\_INC, PARSE\_CMD\_DEC).

If *type* is PARSE\_CMD\_INT, the option requires a second argument on the command-line after the option. This argument is parsed as a number. It can be preceeded by 0x to present a hex-value or by 0 to present an octal form. *addr* is interpreted as an int-pointer. The scanned argument from the command-line is stored in this pointer.

If *type* is PARSE\_CMD\_SWITCH, *addr* must be a pointer to int, and the value from *val* is stored at this pointer.

With PARSE\_CMD\_STRING, an additional argument is expected at the cmdline. *addr* must be a pointer to const char\*, and a pointer to the argument on the command line is stored at this pointer. The value in *val* is a default value, which is stored at *addr* if the corresponding option is not given on the command line.

With PARSE\_CMD\_FN\_ARG, *addr* is interpreted as a function pointer of type `parse_cmd_fn_t`. It will be called with *val* as argument if the corresponding option is found.

If *type* is PARSE\_CMD\_FN\_ARG, *addr* is as a function pointer of type `parse_cmd_fn_arg_t`, and handled similar to PARSE\_CMD\_FN. An additional argument is expected at the command line, however. It is given to the called function as 2nd argument, and parsed as an integer as with PARSE\_CMD\_INT as a third argument.

If *type* is PARSE\_CMD\_INC or PARSE\_CMD\_DEC, *addr* is interpreted as an int-pointer. The value of *val* is stored to this pointer first. For every occurrence of the option in the command line, the integer referenced by *addr* is incremented or decremented, respectively.

The list of command-descriptors is terminated by specifying a binary 0 for the short option char.

Note: The short option char 'h' and the long option name "help" must not be specified. They are used for the default help descriptor and produce a short command-options help when specified on the command-line.

### Parameters

<i>argc</i>	pointer to number of command line parameters as passed to main
<i>argv</i>	pointer to array of command line parameters as passed to main
<i>arg0</i>	format list describing the command line options to parse for

**Returns**

0 if the command-line was successfully parsed, otherwise:


- -1 if the given descriptors are somehow wrong.
- -2 if not enough memory was available to hold temporary structs.
- -3 if the given command-line args did not meet the specified set.
- -4 if the help-option was given.

Upon return, argc and argv point to a list of arguments that were not scanned as arguments. See `getoptlong` for details on scanning.

References [L4\\_CV](#), and [L4\\_END\\_DECLS](#).

**13.16.12 Random number support**

Collaboration diagram for Random number support:

**Functions**

- [l4\\_uint32\\_t](#) `l4util_rand` (void)  
*Deliver next random number.*
- void `l4util_srand` ([l4\\_uint32\\_t](#) seed)  
*Initialize random number generator.*

**13.16.12.1 Detailed Description****13.16.12.2 Function Documentation****13.16.12.2.1 l4util\_rand()**

```
l4_uint32_t l4util_rand (
    void )
```

Deliver next random number.

**Returns**

A new random number

References [L4\\_CV](#).

### 13.16.12.2 l4util\_srand()

```
void l4util_srand (
    l4_uint32_t seed)
```

Initialize random number generator.


#### Parameters

<i>seed</i>	Value to initialize
-------------	---------------------

References [L4\\_END\\_DECLS](#).

### 13.16.13 Low-Level Thread Functions

Collaboration diagram for Low-Level Thread Functions:



## 13.17 Virtio Net Switch

A virtual network switch that can be used as defined in the virtio protocol.

#### Data Structures

- class [Mac\\_addr](#)  
*A wrapper class around the value of a MAC address.*
- class [Mac\\_table](#)< [Size](#) >  
*Mac\_table manages a 1:n association between ports and MAC addresses.*
- class [Switch\\_factory](#)  
*The IPC interface for creating ports.*
- class [L4virtio\\_port](#)  
*A Port on the Virtio Net Switch.*
- class [Net\\_transfer](#)  
*A network request to only a single destination.*
- class [Virtio\\_net\\_request](#)  
*Abstraction for a network request.*
- class [Virtio\\_switch](#)  
*The Virtio switch contains all ports and processes network requests.*
- struct [Buffer](#)  
*Data buffer used to transfer packets.*
- class [Virtio\\_vlan\\_mangle](#)  
*Class for VLAN packet rewriting.*

### 13.17.1 Detailed Description

A virtual network switch that can be used as defined in the virtio protocol.

The abstraction of a single connection with a network device (also called client) from the switch's perspective is a port. A client can register multiple ports on the switch. The communication between a client and the switch happens via IRQs, MMIO and shared memory as defined by the Virtio protocol. The switch supports VLANs and ports can be either 'access' or 'trunk' ports. The optionally available monitor port receives network traffic from all ports, and the monitor can not send.

## 13.18 vCPU Support Library

vCPU handling functionality.

Collaboration diagram for vCPU Support Library:



### Topics

- [Extended vCPU support](#) . . . . . [721](#)  
*Extended vCPU handling functionality.*

### Data Structures

- class [L4vcpu::State](#)  
*C++ implementation of state word in the vCPU area.*
- class [L4vcpu::Vcpu](#)  
*C++ implementation of the vCPU save state area.*

### Functions

- void [l4vcpu\\_irq\\_disable](#) ([l4\\_vcpu\\_state\\_t](#) \*vcpu) [L4\\_NOTHROW](#)  
*Disable a vCPU for event delivery.*
- unsigned [l4vcpu\\_irq\\_disable\\_save](#) ([l4\\_vcpu\\_state\\_t](#) \*vcpu) [L4\\_NOTHROW](#)  
*Disable a vCPU for event delivery and return previous state.*
- void [l4vcpu\\_irq\\_enable](#) ([l4\\_vcpu\\_state\\_t](#) \*vcpu, [l4\\_utcb\\_t](#) \*utcb, [l4vcpu\\_event\\_hdl\\_t](#) do\_event\_work\_cb, [l4vcpu\\_setup\\_ipc\\_t](#) setup\_ipc) [L4\\_NOTHROW](#)  
*Enable a vCPU for event delivery.*
- void [l4vcpu\\_irq\\_restore](#) ([l4\\_vcpu\\_state\\_t](#) \*vcpu, unsigned s, [l4\\_utcb\\_t](#) \*utcb, [l4vcpu\\_event\\_hdl\\_t](#) do\_event\_work\_cb, [l4vcpu\\_setup\\_ipc\\_t](#) setup\_ipc) [L4\\_NOTHROW](#)



*Restore a previously saved IRQ/event state.*

- void [l4vcpu\\_wait\\_for\\_event](#) ([l4\\_vcpu\\_state\\_t](#) \*vcpu, [l4\\_utcb\\_t](#) \*utcb, [l4vcpu\\_event\\_hndl\\_t](#) do\_event\_work←\_cb, [l4vcpu\\_setup\\_ipc\\_t](#) setup\_ipc) [L4\\_NOTHROW](#)

*Wait for event.*

- void [l4vcpu\\_print\\_state](#) (const [l4\\_vcpu\\_state\\_t](#) \*vcpu, const char \*prefix) [L4\\_NOTHROW](#)

*Print the state of a vCPU.*

- int [l4vcpu\\_is\\_irq\\_entry](#) ([l4\\_vcpu\\_state\\_t](#) const \*vcpu) [L4\\_NOTHROW](#)

*Return whether the entry reason was an IRQ/IPC message.*

- int [l4vcpu\\_is\\_page\\_fault\\_entry](#) ([l4\\_vcpu\\_state\\_t](#) const \*vcpu) [L4\\_NOTHROW](#)

*Return whether the entry reason was a page fault.*

## 13.18.1 Detailed Description

vCPU handling functionality.

This library provides convenience functionality on top of the l4sys vCPU interface to ease programming. It wraps commonly used code and abstracts architecture depends parts as far as reasonable.

## 13.18.2 Function Documentation

### 13.18.2.1 l4vcpu\_irq\_disable()

```
void l4vcpu_irq_disable (
    l4\_vcpu\_state\_t * vcpu) [inline]
```

Disable a vCPU for event delivery.

#### Parameters

<i>vcpu</i>	Pointer to vCPU area.
-------------	-----------------------

Definition at line 201 of file [vcpu.h](#).


References [l4\\_barrier\(\)](#), [L4\\_NOTHROW](#), and [L4\\_VCPU\\_F\\_IRQ](#).

Referenced by [L4vcpu::Vcpu::irq\\_disable\(\)](#), [l4vcpu\\_irq\\_disable\\_save\(\)](#), and [l4vcpu\\_irq\\_restore\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 13.18.2.2 l4vcpu\_irq\_disable\_save()

```

unsigned l4vcpu_irq_disable_save (
    l4_vcpu_state_t * vcpu) [inline]
  
```

Disable a vCPU for event delivery and return previous state.

#### Parameters

<i>vcpu</i>	Pointer to vCPU area.
-------------	-----------------------

#### Returns


IRQ state before disabling IRQs.

Definition at line 209 of file [vcpu.h](#).


References [L4\\_NOTHROW](#), and [l4vcpu\\_irq\\_disable\(\)](#).

Referenced by [L4vcpu::Vcpu::irq\\_disable\\_save\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 13.18.2.3 l4vcpu\_irq\_enable()

```
void l4vcpu_irq_enable (
    l4_vcpu_state_t * vcpu,
    l4_utcb_t * utcb,
    l4vcpu_event_hndl_t do_event_work_cb,
    l4vcpu_setup_ipc_t setup_ipc) [inline]
```

Enable a vCPU for event delivery.

#### Parameters


<i>vcpu</i>	Pointer to vCPU area.
<i>utcb</i>	Utcbl pointer of the calling vCPU.
<i>do_event_work_cb</i>	Call-back function that is called in case an event (such as an interrupt) is pending.
<i>setup_ipc</i>	Function call-back that is called right before any IPC operation, and before event delivery is enabled.

Definition at line 232 of file [vcpu.h](#).


References [l4\\_barrier\(\)](#), [L4\\_IPC\\_BOTH\\_TIMEOUT\\_0](#), [L4\\_LIKELY](#), [L4\\_NOTHROW](#), [L4\\_VCPU\\_F\\_IRQ](#), and [L4\\_VCPU\\_SF\\_IRQ\\_PENDING](#).

Referenced by [L4vcpu::Vcpu::irq\\_enable\(\)](#), and [l4vcpu\\_irq\\_restore\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 13.18.2.4 l4vcpu\_irq\_restore()

```
void l4vcpu_irq_restore (
    l4_vcpu_state_t * vcpu,
    unsigned s,
    l4_utcb_t * utcb,
    l4vcpu_event_hndl_t do_event_work_cb,
    l4vcpu_setup_ipc_t setup_ipc) [inline]
```

Restore a previously saved IRQ/event state.

#### Parameters


<i>vcpu</i>	Pointer to vCPU area.
<i>s</i>	IRQ state to be restored.
<i>utcb</i>	Utcbl pointer of the calling vCPU.
<i>do_event_work_cb</i>	Call-back function that is called in case an event (such as an interrupt) is pending after enabling.
<i>setup_ipc</i>	Function call-back that is called right before any IPC operation, and before event delivery is enabled.

Definition at line 257 of file [vcpu.h](#).

References [L4\\_NOTHROW](#), [L4\\_VCPU\\_F\\_IRQ](#), [l4vcpu\\_irq\\_disable\(\)](#), and [l4vcpu\\_irq\\_enable\(\)](#).

Referenced by [L4vcpu::Vcpu::irq\\_restore\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 13.18.2.5 l4vcpu\_is\_irq\_entry()

```
int l4vcpu_is_irq_entry (  
    l4_vcpu_state_t const * vcpu) [inline]
```

Return whether the entry reason was an IRQ/IPC message.

#### Parameters


<i>vcpu</i>	Pointer to vCPU area.
-------------	-----------------------

return 0 if not, !=0 otherwise.

References [L4\\_CV](#), [L4\\_INLINE](#), and [L4\\_NOTHROW](#).

Referenced by [L4vcpu::Vcpu::is\\_irq\\_entry\(\)](#).

Here is the caller graph for this function:



### 13.18.2.6 l4vcpu\_is\_page\_fault\_entry()

```
int l4vcpu_is_page_fault_entry (  
    l4_vcpu_state_t const * vcpu) [inline]
```

Return whether the entry reason was a page fault.

#### Parameters


<i>vcpu</i>	Pointer to vCPU area.
-------------	-----------------------

return 0 if not, !=0 otherwise.

References [L4\\_CV](#), and [L4\\_NOTHROW](#).

Referenced by [L4vcpu::Vcpu::is\\_page\\_fault\\_entry\(\)](#).

Here is the caller graph for this function:



### 13.18.2.7 l4vcpu\_print\_state()

```
void l4vcpu_print_state (
    const l4_vcpu_state_t * vcpu,
    const char * prefix)
```

Print the state of a vCPU.


#### Parameters

<i>vcpu</i>	Pointer to vCPU area.
<i>prefix</i>	A prefix for each line printed.

References [L4\\_CV](#), [L4\\_INLINE](#), and [L4\\_NOTHROW](#).

Referenced by [L4vcpu::Vcpu::print\\_state\(\)](#).

Here is the caller graph for this function:



### 13.18.2.8 l4vcpu\_wait\_for\_event()

```
void l4vcpu_wait_for_event (
    l4_vcpu_state_t * vcpu,
    l4_utcb_t * utcb,
    l4vcpu_event_hndl_t do_event_work_cb,
    l4vcpu_setup_ipc_t setup_ipc) [inline]
```

Wait for event.

### Parameters

<i>vcpu</i>	Pointer to vCPU area.
<i>utcb</i>	Utc b pointer of the calling vCPU.
<i>do_event_work_cb</i>	Call-back function that is called when the vCPU awakes and needs to handle an event/↔ IRQ.
<i>setup_ipc</i>	Function call-back that is called right before any IPC operation.


Note that event delivery remains disabled after this function returns.

Definition at line 270 of file [vcpu.h](#).

References [L4\\_IPC\\_NEVER](#), and [L4\\_NOTHROW](#).

Referenced by [L4vcpu::Vcpu::wait\\_for\\_event\(\)](#).


Here is the caller graph for this function:



### 13.18.3 Extended vCPU support

Extended vCPU handling functionality.

Collaboration diagram for Extended vCPU support:



### Functions

- [int l4vcpu\\_ext\\_alloc](#) ([l4\\_vcpu\\_state\\_t](#) \*\*vcpu, [l4\\_addr\\_t](#) \*ext\_state, [l4\\_cap\\_idx\\_t](#) task, [l4\\_cap\\_idx\\_t](#) regmgr)  
[L4\\_NOTHROW](#)  
*Allocate state area for an extended vCPU.*

### 13.18.3.1 Detailed Description

Extended vCPU handling functionality.

### 13.18.3.2 Function Documentation

#### 13.18.3.2.1 l4vcpu\_ext\_alloc()

```
int l4vcpu_ext_alloc (
    l4_vcpu_state_t ** vcpu,
    l4_addr_t * ext_state,
    l4_cap_idx_t task,
    l4_cap_idx_t regmgr)
```

Allocate state area for an extended vCPU.

#### Parameters

out	<i>vcpu</i>	Allocated vcpu-state area.
out	<i>ext_state</i>	Allocated extended vcpu-state area.
	<i>task</i>	Task to use for allocation.
	<i>regmgr</i>	Region manager to use for allocation.

#### Returns

0 for success, error code otherwise

References [L4\\_CV](#), [L4\\_INLINE](#), and [L4\\_NOTHROW](#).



# Chapter 14

## Namespace Documentation

### 14.1 cxx Namespace Reference

Our C++ library.

#### Namespaces

- namespace [Bits](#)  
*Internal helpers for the cxx package.*

#### Data Structures

- class [Avl\\_map](#)  
*AVL tree based associative container.*
- class [Avl\\_set](#)  
*AVL set for simple comparable items.*
- class [Avl\\_tree\\_node](#)  
*Node of an AVL tree.*
- class [Avl\\_tree](#)  
*A generic AVL tree.*
- class [Bitfield](#)  
*Definition for a member (part) of a bit field.*
- class [Bitmap\\_base](#)  
*Basic bitmap abstraction.*
- class [Bitmap](#)  
*A static bitmap.*
- class [Elide\\_dtor](#)  
*Wrapper class to remove destructor calls.*
- class [H\\_list\\_item\\_t](#)  
*Basic element type for a double-linked [H\\_list](#).*
- class [H\\_list](#)  
*General double-linked list of unspecified [cxx::H\\_list\\_item](#) elements.*
- struct [H\\_list\\_t](#)  
*Double-linked list of typed [H\\_list\\_item\\_t](#) elements.*

- class [List\\_item](#)  
*Basic list item.*
- class [List](#)  
*Doubly linked list, with internal allocation.*
- class [List\\_alloc](#)  
*Standard list-based allocator.*
- struct [Pair](#)  
*Pair of two values.*
- class [Pair\\_first\\_compare](#)  
*Comparison functor for [Pair](#).*
- class [Ref\\_ptr](#)  
*A reference-counting pointer with automatic cleanup.*
- struct [Ref\\_obj\\_list\\_item](#)  
*Item for list linked via [cxx::Ref\\_ptr](#) with default reference counting.*
- class [Base\\_slab](#)  
*Basic slab allocator.*
- class [Slab](#)  
*Slab allocator for object of type `Type`.*
- class [Base\\_slab\\_static](#)  
*Merged slab allocator (allocators for objects of the same size are merged together).*
- class [Slab\\_static](#)  
*Merged slab allocator (allocators for objects of the same size are merged together).*
- class [S\\_list](#)  
*Simple single-linked list.*
- class [static\\_vector](#)  
*Simple encapsulation for a dynamically allocated array.*
- class [Nothrow](#)  
*Helper type to distinguish the `operator new` version that does not throw exceptions.*
- class [New\\_allocator](#)  
*Standard allocator based on `operator new ()`.*
- struct [Lt\\_functor](#)  
*Generic comparator class that defaults to the less-than operator.*
- class [String](#)  
*Allocation free string class with explicit length field.*
- class [Weak\\_ref\\_base](#)  
*Generic (base) weak reference to some object.*
- class [Weak\\_ref](#)  
*Typed weak reference to an object of type `T`.*

## Typedefs

- typedef [H\\_list\\_item\\_t](#)< void > [H\\_list\\_item](#)  
*Untyped list item.*
- template<typename T>  
using [Ref\\_ptr\\_list\\_item](#) = [Bits::Smart\\_ptr\\_list\\_item](#)<T, [cxx::Ref\\_ptr](#)<T> >  
*Item for list linked with [cxx::Ref\\_ptr](#).*
- template<typename T>  
using [Ref\\_ptr\\_list](#) = [Bits::Smart\\_ptr\\_list](#)<[Ref\\_ptr\\_list\\_item](#)<T> >  
*Single-linked list where elements are connected via a [cxx::Ref\\_ptr](#).*

- `template<typename T>`  
`using Unique_ptr_list_item = Bits::Smart_ptr_list_item<T, cxx::unique_ptr<T> >`  
*Item for list linked with cxx::unique\_ptr.*
- `template<typename T>`  
`using Unique_ptr_list = Bits::Smart_ptr_list<Unique_ptr_list_item<T> >`  
*Single-linked list where elements are connected with a cxx::unique\_ptr.*

## Functions

- `template<typename A, typename ... ARGS>`  
`constexpr A const & min (A const &a1, A const &a2, ARGS const &...a)`  
*Get the minimum of a1 and a2 upt to aN.*
- `template<typename A, typename ... ARGS>`  
`constexpr A const & min (cxx::identity_t< A > const &a1, cxx::identity_t< A > const &a2, ARGS const &...a)`  
*Get the minimum of a1 and a2 upt to aN.*
- `template<typename A, typename ... ARGS>`  
`constexpr A const & max (A const &a1, A const &a2, ARGS const &...a)`  
*Get the maximum of a1 and a2 upt to aN.*
- `template<typename A, typename ... ARGS>`  
`constexpr A const & max (cxx::identity_t< A > const &a1, cxx::identity_t< A > const &a2, ARGS const &...a)`  
*Get the maximum of a1 and a2 upt to aN.*
- `template<typename T1>`  
`T1 clamp (T1 v, T1 lo, T1 hi)`  
*Limit v to the range given by lo and hi.*
- `template<typename T>`  
`constexpr T gcd (T a, T b)`  
*Compute the greatest common divisor of two unsigned values.*
- `template<typename T>`  
`constexpr T lcm (T a, T b)`  
*Compute the least common multiple of two unsigned values.*
- `template<typename T>`  
`T access_once (T const *a)`  
*Read the value at an address at most once.*
- `template<typename T, typename VAL>`  
`void write_now (T *a, VAL &&val)`  
*Write a value at an address exactly once.*

### 14.1.1 Detailed Description

Our C++ library.

Small Low-Level C++ Library.

Strings.

Various kinds of C++ utilities.

## 14.1.2 Function Documentation

### 14.1.2.1 access\_once()

```
template<typename T>
T cxx::access_once (
    T const * a) [inline]
```

Read the value at an address at most once.

The read might be omitted if the result is not used by any code unless `typename` contains `volatile`. If the read operation has side effects and must not be omitted, use different means like [L4drivers::Mmio\\_register\\_block](#) or similar.

The compiler is disallowed to reuse a previous read at the same address, for example:

```
val1 = *a;
val2 = access_once(a); // compiler may not replace this by val2 = val1;
```

The compiler is also disallowed to repeat the read, for example:

```
val1 = access_once(a);
val2 = val1; // compiler may not replace this by val2 = *a;
```

The above implies that the compiler is also disallowed to move the read out of or into loops.

#### Note


The read might still be moved relative to other code.

The value might be read from a hardware cache, not from RAM.

Definition at line 40 of file [utils](#).

Referenced by [L4virtio::Svr::Request\\_processor::next\(\)](#), and [L4virtio::Svr::Request\\_processor::start\(\)](#).

Here is the caller graph for this function:



### 14.1.2.2 gcd()

```
template<typename T>
T cxx::gcd (
    T a,
    T b) [constexpr]
```

Compute the greatest common divisor of two unsigned values.

This uses the Euclidean modulo algorithm.

#### Note

Contrary to the C++17 specification, this implementation requires the same unsigned type of both arguments and returns the same type (not a common type). This should be fine for most practical use cases.

Contrary to the C++17 specification, this implementation does not accept signed arguments and negative literals.

#### Template Parameters

<i>T</i>	Unsigned integer type of the values.
----------	--------------------------------------

#### Parameters

<i>a</i>	First input.
<i>b</i>	Second input.

#### Returns

Greatest common divisor of the input values.

Definition at line 34 of file [numeric](#).

Referenced by [lcm\(\)](#).

Here is the caller graph for this function:



### 14.1.2.3 lcm()

```
template<typename T>
T cxx::lcm (
    T a,
    T b) [constexpr]
```

Compute the least common multiple of two unsigned values.

This uses the greatest common divisor to compute the least common multiple.

#### Note

Contrary to the C++17 specification, this implementation requires the same unsigned type of both arguments and returns the same type (not a common type). This should be fine for most practical use cases.

Contrary to the C++17 specification, this implementation does not accept signed arguments and negative literals.

#### Template Parameters

<i>T</i>	Unsigned integer type of the values.
----------	--------------------------------------

#### Parameters

<i>a</i>	First input.
<i>b</i>	Second input.

#### Returns

Least common multiple of the input values.

Definition at line 68 of file [numeric](#).

References [gcd\(\)](#).

Here is the call graph for this function:



#### 14.1.2.4 write\_now()

```
template<typename T, typename VAL>
void cxx::write_now (
    T * a,
    VAL && val) [inline]
```

Write a value at an address exactly once.

The compiler is disallowed to skip the write, for example:

```
*a = val;
write_now(a, val); // compiler may not skip this line
```

The compiler is also disallowed to repeat the write.

The above implies that the compiler is also disallowed to move the write out of or into loops.

#### Note

The write might still be moved relative to other code.

The value might be written just to a hardware cache for the moment, not immediately to RAM.

Definition at line 71 of file [utils](#).

## 14.2 cxx::Bits Namespace Reference

Internal helpers for the cxx package.

### Data Structures

- struct [Avl\\_map\\_get\\_key](#)  
*Key-getter for [Avl\\_map](#).*
- class [Avl\\_set\\_iter](#)  
*Generic iterator for the AVL-tree based set.*
- struct [Avl\\_set\\_get\\_key](#)  
*Internal, key-getter for [Avl\\_set](#) nodes.*
- class [Base\\_avl\\_set](#)  
*AVL set with internally managed nodes.*
- class [Bst](#)  
*Basic binary search tree (BST).*
- struct [Direction](#)  
*The direction to go in a binary search tree.*
- class [Bst\\_node](#)  
*Basic type of a node in a binary search tree (BST).*
- class [Basic\\_list](#)  
*Internal: Common functions for all head-based list implementations.*
- class [Smart\\_ptr\\_list\\_item](#)  
*List item for an arbitrary item in a [Smart\\_ptr\\_list](#).*
- class [Smart\\_ptr\\_list](#)  
*List of smart-pointer-managed objects.*

### 14.2.1 Detailed Description

Internal helpers for the cxx package.

## 14.3 Enum\_bitops Namespace Reference

Mechanism to opt-in for enum bitwise operators.

### Data Structures

- struct [Has\\_marker](#)  
*Marker for the opt-in ADL function.*
- struct [Has\\_marker](#)< T, Void< decltype(enum\_bitops\_enable(declval< T >()))> >  
*Marker for the opt-in ADL function.*
- struct [Enable](#)  
*Check whether the given enum type opts in for the bitwise operators.*

### 14.3.1 Detailed Description

Mechanism to opt-in for enum bitwise operators.

For an enumeration type T to opt-in for bitwise operators, there needs to be a declaration of a function

```
void enum_bitops_enable(T)
```

available for the argument-dependent lookup (the function is never actually called, thus no definition is required and no code is generated).

## 14.4 Enum\_bitops\_impl Namespace Reference

Bitwise operators on enumeration types.

### Functions

- template<typename T, typename = L4::Types::Enable\_if\_t<L4::Types::Is\_enum<T>::value>>  
constexpr [L4::Types::Underlying\\_type\\_t](#)< T > **to\_underlying** (T const arg) noexcept  
*Convert enum value to its underlying type value.*
- template<typename T, typename = L4::Types::Enable\_if\_t<Enum\_bitops::Enable<T>::value>>  
constexpr T **operator~** (T const a) noexcept  
*Negate enum value.*
- template<typename T, typename = L4::Types::Enable\_if\_t<Enum\_bitops::Enable<T>::value>>  
constexpr T **operator&** (T l, T r) noexcept  
*Intersect enum values.*
- template<typename T, typename = L4::Types::Enable\_if\_t<Enum\_bitops::Enable<T>::value>>  
constexpr T & **operator&=** (T &a, T const b) noexcept  
*Intersect and assign enum values.*



- `template<typename T, typename = L4::Types::Enable_if_t<Enum_bitops::Enable<T>::value>>`  
`constexpr T operator| (T l, T r) noexcept`  
*Union enum values.*
- `template<typename T, typename = L4::Types::Enable_if_t<Enum_bitops::Enable<T>::value>>`  
`constexpr T & operator|= (T &a, T const b) noexcept`  
*Union and assign enum values.*
- `template<typename T, typename = L4::Types::Enable_if_t<Enum_bitops::Enable<T>::value>>`  
`constexpr T operator- (T l, T r) noexcept`  
*Difference (intersect with negation, clear bits) enum values.*
- `template<typename T, typename = L4::Types::Enable_if_t<Enum_bitops::Enable<T>::value>>`  
`constexpr T & operator-= (T &a, T const b) noexcept`  
*Difference (intersect with negation, clear bits) and assign enum values.*

### 14.4.1 Detailed Description

Bitwise operators on enumeration types.

These operators allow to use the enum type as a bitmask type with '~', '&' and '|' operators that keep the enum type as result. The compound assignment operators '&=' and '|=' are also provided.

The set-difference '-' and '-=' operators (a shorthand for intersection with a negated second argument) can be used to clear specific bits from the enum value. There is also the [to\\_underlying\(\)](#) helper function.

## 14.5 L4 Namespace Reference

[L4](#) low-level kernel interface.

### Namespaces

- namespace [Typeid](#)  
*Definition of interface data-type helpers.*
- namespace [lpc](#)  
*IPC related functionality.*
- namespace [lpc\\_svr](#)  
*Helper classes for [L4::Server](#) instantiation.*
- namespace [Types](#)  
[L4](#) basic type helpers for C++.

## Data Structures

- struct [Type\\_info](#)  
*Dynamic Type Information for [L4Re](#) Interfaces.*
- struct [Kobject\\_typeid](#)  
*Meta object for handling access to type information of Kobjects.*
- struct [Kobject\\_typeid< void >](#)  
*Minimalistic ID for `void` interface.*
- class [Kobject\\_t](#)  
*Helper class to create an [L4Re](#) interface class that is derived from a single base class.*
- class [Kobject\\_2t](#)  
*Helper class to create an [L4Re](#) interface class that is derived from two base classes (see [L4::Kobject\\_t](#)).*
- struct [Kobject\\_3t](#)  
*Helper class to create an [L4Re](#) interface class that is derived from three base classes (see [L4::Kobject\\_t](#)).*
- struct [Kobject\\_demand](#)  
*Get the combined server-side resource requirements for all type `T...`*
- struct [Proto\\_t](#)  
*Data type for defining protocol numbers.*
- struct [Kobject\\_x](#)  
*Generic [Kobject](#) inheritance template.*
- class [Arm\\_smccc](#)  
*Wrapper for function calls that follow the ARM SMC/HVC calling convention.*
- class [Cap](#)  
*C++ interface for capabilities.*
- class [Cap\\_base](#)  
*Base class for all kinds of capabilities.*
- struct [Epiface](#)  
*Base class for interface implementations.*
- struct [Epiface\\_t0](#)  
*[Epiface](#) mixin for generic [Kobject](#)-based interfaces.*
- struct [Irqep\\_t](#)  
*[Epiface](#) implementation for interrupt handlers.*
- class [Registry\\_iface](#)  
*Abstract interface for object registries.*
- struct [Epiface\\_t](#)  
*[Epiface](#) implementation for [Kobject](#)-based interface implementations.*
- class [Basic\\_registry](#)  
*This registry returns the corresponding server object based on the label of an [lpc\\_gate](#).*
- class [Server](#)  
*Basic server loop for handling client requests.*
- class [Debugger](#)  
*C++ kernel debugger API.*
- class [Exception](#)  
*[Exception](#) interface.*
- class [Factory](#)  
*C++ Factory interface, see [Factory](#) for the C interface.*
- class [lommu](#)  
*Interface for IO-MMUs used for DMA remapping.*
- class [lpc\\_gate](#)  
*The C++ IPC gate interface, see [IPC-Gate API](#) for the C interface.*
- class [Irq\\_eoi](#)

- Interface for sending an unmask message to an object.*

  - struct [Triggerable](#)
- Interface that allows an object to be triggered by some source.*

  - class [Irq](#)
    - C++ [Irq](#) interface, see [IRQs](#) for the C interface.*
  - class [Icu](#)
    - C++ [Icu](#) interface, see [Interrupt controller](#) for the C interface.*
  - class [Kobject](#)
    - Base class for all kinds of kernel objects and remote objects, referenced by capabilities.*
  - class [Meta](#)
    - [Meta](#) interface that shall be implemented by each [L4Re](#) object and gives access to the dynamic type information for [L4Re](#) objects.*
  - class [lo\\_pager](#)
    - [lo\\_pager](#) interface.*
  - class [Pager](#)
    - [Pager](#) interface including the [lo\\_pager](#) interface.*
  - class [Platform\\_control](#)
    - [L4](#) C++ interface for controlling platform-wide properties, see [Platform Control C API](#) for the C interface.*
  - class [Rcv\\_endpoint](#)
    - Interface for kernel objects that allow to receive IPC from them.*
  - class [Scheduler](#)
    - C++ interface of the [Scheduler](#) kernel object, see [Scheduler](#) for the C interface.*
  - struct [Semaphore](#)
    - C++ Kernel-provided semaphore interface, see [Kernel-provided semaphore](#) for the C interface.*
  - class [Smart\\_cap](#)
    - Smart capability class.*
  - class [Task](#)
    - C++ interface of the [Task](#) kernel object, see [Task](#) for the C interface.*
  - class [Thread](#)
    - C++ [L4](#) kernel thread interface, see [Thread](#) for the C interface.*
  - class [Thread\\_group](#)
    - C++ [L4](#) kernel thread group interface, see [Thread groups](#) for the C interface.*
  - class [Vcon](#)
    - C++ [L4 Vcon](#) interface, see [Virtual Console](#) for the C interface.*
  - class [Vm](#)
    - Virtual machine host address space.*
  - class [Poll\\_timeout\\_kipclock](#)
    - A polling timeout based on the [L4Re](#) clock.*
  - class [Alloc\\_list](#)
    - A simple list-based allocator.*
  - class [IOModifier](#)
    - Modifier class for the IO stream.*
  - class [Exception\\_tracer](#)
    - Back-trace support for exceptions.*
  - class [Base\\_exception](#)
    - Base class for all exceptions, thrown by the [L4Re](#) framework.*
  - class [Runtime\\_error](#)
    - [Exception](#) for an abstract runtime error.*
  - class [Out\\_of\\_memory](#)
    - [Exception](#) signalling insufficient memory.*
  - class [Element\\_already\\_exists](#)

- Exception for duplicate element insertions.*
- class `Unknown_error`
  - Exception for an unknown condition.*
- class `Element_not_found`
  - Exception for a failed lookup (element not found).*
- class `Invalid_capability`
  - Indicates that an invalid object was invoked.*
- class `Com_error`
  - Error conditions during IPC.*
- class `Bounds_error`
  - Access out of bounds.*
- class `Server_object`
  - Abstract server object to be used with `L4::Server` and `L4::Basic_registry`.*
- struct `Server_object_t`
  - Base class (template) for server implementing server objects.*
- struct `Server_object_x`
  - Helper class to implement p\_dispatch based server objects.*
- struct `Irq_handler_object`
  - Server object base class for handling IRQ messages.*
- class `Lock_guard`
  - Basic lock guard implementation that prevents forgotten unlocks on exit paths from a method or a block of code.*
- class `String`
  - A null-terminated string container class.*
- class `Poll_timeout_counter`
  - Evaluate an expression for a maximum number of times.*
- class `Uart_apb`
  - Driver for the Advanced Peripheral Bus (APB) UART from the Cortex-M System Design Kit (CMSDK).*
- class `Uart`
  - Uart driver abstraction.*

## Typedefs

- typedef int `Opcode`
  - Data type for RPC opcodes.*

## Enumerations

- enum : `l4_proto_t` { `PROTO_ANY` = 0 , `PROTO_EMPTY` = -19 }

## Functions

- template<typename T>  
`Type_info` const \* `kobject_typeid` () noexcept  
*Get the `L4::Type_info` for the `L4Re` interface given in `T`.*
- template<typename T, typename F>  
`Cap`< T > `cap_dynamic_cast` (`Cap`< F > const &c) noexcept  
*dynamic\_cast for capabilities.*
- template<typename T, typename F>  
`Cap`< T > `cap_cast` (`Cap`< F > const &c) noexcept

- static\_cast* for capabilities.

  - `template<typename T, typename F>`  
`Cap< T > cap_reinterpret_cast (Cap< F > const &c) noexcept`  
*reinterpret\_cast* for capabilities.
- `template<typename T>`  
`constexpr T trunc_order (T val, unsigned char order)`  
*Round a value down so the given number of lsb is zero.*
- `template<typename T>`  
`constexpr T round_order (T val, unsigned char order)`  
*Round a value up so the given number of lsb is zero.*
- `template<typename T, typename F, typename SMART>`  
`Smart_cap< T, SMART > cap_cast (Smart_cap< F, SMART > const &c) noexcept`  
*static\_cast* for (smart) capabilities.
- `template<typename T, typename F, typename SMART>`  
`Smart_cap< T, SMART > cap_reinterpret_cast (Smart_cap< F, SMART > const &c) noexcept`  
*reinterpret\_cast* for (smart) capabilities.
- `void throw_ipc_exception (L4::Cap< void > const &o, l4_msgtag_t const &err, l4_utcb_t *utcb)`  
*Throw an L4 IPC error as exception.*
- `void throw_ipc_exception (void const *o, l4_msgtag_t const &err, l4_utcb_t *utcb)`  
*Throw an L4 IPC error as exception.*

## Variables

- `IOModifier` const **hex**  
*Modifies the stream to print numbers as hexadecimal values.*
- `IOModifier` const **dec**  
*Modifies the stream to print numbers as decimal values.*
- `BasicOStream` **cout**  
*Standard output stream.*
- `BasicOStream` **cerr**  
*Standard error stream.*

## 14.5.1 Detailed Description

[L4](#) low-level kernel interface.

## 14.5.2 Enumeration Type Documentation

### 14.5.2.1 anonymous enum

anonymous enum : `l4_proto_t`

#### Enumerator

PROTO_ANY	Default protocol used by <code>Kobject_t</code> and <code>Kobject_x</code> .
PROTO_EMPTY	Empty protocol for empty APIs.

Definition at line 44 of file `__typeinfo.h`.

### 14.5.3 Function Documentation

#### 14.5.3.1 `cap_cast()` [1/2]

```
template<typename T, typename F>
Cap< T > L4::cap_cast (
    Cap< F > const & c) [inline], [noexcept]
```

`static_cast` for capabilities.

#### Template Parameters

<i>T</i>	The target type of the capability
<i>F</i>	The source type (and is usually implicitly set)

#### Parameters

<i>c</i>	The source capability that shall be casted
----------	--

#### Returns

A capability typed to the interface *T*.

The use of this cast operator is similar to the `static_cast<>()` for C++ pointers. It does the same type checking and adjustments like C++ does on pointers.


Example code:

```
L4::Cap<L4::Kobject> obj = ... ;
L4::Cap<L4::Icu> icu = L4::cap_cast<L4::Icu>(obj);
```

Definition at line 416 of file [capability.h](#).

Referenced by [L4Re::Cap\\_alloc::alloc\(\)](#), [L4Re::Util::\\_Cap\\_alloc::alloc\(\)](#), [L4Re::Util::Counting\\_cap\\_alloc< COUNTERTYPE, Dbg >::a](#), [L4virtio::Svr::Virtio\\_gpio< Request\\_handler, Epiface >::device\\_notify\\_irq\(\)](#), [L4virtio::Svr::Virtio\\_i2c< Request\\_handler, Epiface >::d](#), [L4virtio::Svr::Virtio\\_rng< Rnd\\_state, Epiface >::device\\_notify\\_irq\(\)](#), [L4virtio::Svr::Virtio\\_spi< Spi\\_request\\_handler, Epiface >::device](#), [L4::Epiface\\_t0< RPC\\_IFACE, BASE >::obj\\_cap\(\)](#), [L4::lrqep\\_t< Derived, BASE, bool >::obj\\_cap\(\)](#), and [L4::lpc\\_svr::Server\\_iface::rcv](#)

Here is the caller graph for this function:



### 14.5.3.2 `cap_cast()` [2/2]

```

template<typename T, typename F, typename SMART>
Smart_cap< T, SMART > L4::cap_cast (
    Smart_cap< F, SMART > const & c) [inline], [noexcept]

```

`static_cast` for (smart) capabilities.

**Template Parameters**

<i>T</i>	Type to cast the capability to.
<i>F</i>	(implicit) Type of the passed capability.
<i>SMART</i>	(implicit) Class implementing the <a href="#">Smart_cap</a> interface.

**Parameters**

<i>c</i>	Capability to be casted.
----------	--------------------------

**Returns**

A smart capability with new type *T*.

Definition at line 192 of file [smart\\_capability](#).

**14.5.3.3 cap\_dynamic\_cast()**

```
template<typename T, typename F>
Cap< T > L4::cap_dynamic_cast (
    Cap< F > const & c) [inline], [noexcept]
```

`dynamic_cast` for capabilities.

**Template Parameters**

<i>T</i>	The target type of the capability.
<i>F</i>	The source type (is usually implicitly set).

**Parameters**

<i>c</i>	The source capability that shall be casted.
----------	---

**Return values**

<a href="#">Cap&lt;T&gt;</a>	Capability of target interface <i>T</i> .
<i>L4_INVALID_CAP</i>	<i>c</i> does not support the target interface <i>T</i> or the <a href="#">L4::Meta</a> interface.

The use of this cast operator is similar to the `dynamic_cast<>()` for C++ pointers. It also induces overhead, because it uses the meta interface ([L4::Meta](#)) to do runtime type checking.

Example code:


```
L4::Cap<L4::Kobject> obj = ... ;
L4::Cap<L4::Icu> icu = L4::cap_dynamic_cast<L4::Icu>(obj);
```



Definition at line 116 of file [capability](#).

References [cap\\_reinterpret\\_cast\(\)](#), [L4::Cap\\_base::Invalid](#), [kobject\\_typeid\(\)](#), and [l4\\_error\(\)](#).

Here is the call graph for this function:



#### 14.5.3.4 cap\_reinterpret\_cast() [1/2]

```

template<typename T, typename F>
Cap< T > L4::cap_reinterpret_cast (
    Cap< F > const & c) [inline], [noexcept]
  
```

reinterpret\_cast for capabilities.

##### Template Parameters

<i>T</i>	The target type of the capability
<i>F</i>	The source type (and is usually implicitly set)

##### Parameters

<i>c</i>	The source capability that shall be casted
----------	--

##### Returns

A capability typed to the interface *T*.

The use of this cast operator is similar to the `reinterpret_cast<>()` for C++ pointers. It does not do any type checking or type adjustment.

Example code:

```

L4::Cap<L4::Kobject> obj = ... ;
L4::Cap<L4::Icu> icu = L4::cap_reinterpret_cast<L4::Icu>(obj);
  
```

Definition at line 447 of file [capability.h](#).

Referenced by [cap\\_dynamic\\_cast\(\)](#).

Here is the caller graph for this function:



#### 14.5.3.5 cap\_reinterpret\_cast() [2/2]

```
template<typename T, typename F, typename SMART>
Smart_cap< T, SMART > L4::cap_reinterpret_cast (
    Smart_cap< F, SMART > const & c) [inline], [noexcept]
```

reinterpret\_cast for (smart) capabilities.

##### Template Parameters

<i>T</i>	Type to cast the capability to.
<i>F</i>	(implicit) Type of the passed capability.
<i>SMART</i>	(implicit) Class implementing the <a href="#">Smart_cap</a> interface.

##### Parameters

<i>c</i>	Capability to be casted.
----------	--------------------------

##### Returns

A smart capability with new type *T*.

Definition at line 211 of file [smart\\_capability](#).

#### 14.5.3.6 round\_order()

```
template<typename T>
T L4::round_order (
    T val,
    unsigned char order) [constexpr]
```

Round a value up so the given number of lsb is zero.

### Template Parameters

<i>T</i>	The type of the value (shall be some integral type).
----------	--

### Parameters

<i>val</i>	The value to round up to the next multiple of $2^{\text{order}}$ .
<i>order</i>	order ( $2^{\text{order}}$ ) to round up to.


### Returns

val rounded up to the next  $2^{\text{order}}$ .

Definition at line 32 of file [consts](#).

Referenced by [L4Re::Dataspace::map\\_region\(\)](#).

Here is the caller graph for this function:



#### 14.5.3.7 trunc\_order()

```
template<typename T>
T L4::trunc_order (
    T val,
    unsigned char order) [constexpr]
```

Round a value down so the given number of lsb is zero.

### Template Parameters

<i>T</i>	The type of the value (shall be some integral type).
----------	--

### Parameters

<i>val</i>	The value where the given lsb shall be masked.
------------	--

<i>order</i>	the number of least significant bits (lsb) to mask.
--------------	---


**Returns**

val with order lsb masked to zero.

Definition at line 18 of file [consts](#).

Referenced by [L4Re::Dataspace::map\\_region\(\)](#).

Here is the caller graph for this function:



## 14.6 L4::lpc Namespace Reference

IPC related functionality.

**Namespaces**

- namespace [Msg](#)  
*IPC Message related functionality.*

**Data Structures**

- struct [Array\\_ref](#)  
*[Array](#) reference data type for arrays located in the message.*
- struct [Array](#)  
*[Array](#) data type for dynamically sized arrays in RPCs.*
- struct [Array\\_in\\_buf](#)  
*Server-side copy in buffer for [Array](#).*
- struct [Call](#)  
*RPC attribute for a standard RPC call.*
- struct [Call\\_zero\\_send\\_timeout](#)  
*RPC attribute for an RPC call, with zero send timeout.*
- struct [Call\\_t](#)  
*RPC attribute for an RPC call with required rights.*
- struct [Send\\_only](#)  
*RPC attribute for a send-only RPC.*

- struct [Ret\\_array](#)  
*Dynamically sized output array of type T.*
- struct [Out](#)  
*Mark an argument as a output value in an RPC signature.*
- struct [In\\_out](#)  
*Mark an argument as in-out argument.*
- struct [As\\_value](#)  
*Pass the argument as plain data value.*
- struct [Opt](#)  
*Attribute for defining an optional RPC argument.*
- class [Small\\_buf](#)  
*A receive item for receiving a single object capability.*
- class [Gen\\_fpage](#)  
*Generic RPC base for typed message items.*
- class [Snd\\_fpage](#)  
*Send item or return item.*
- class [Rcv\\_fpage](#)  
*Non-small receive item.*
- class [Cap](#)  
*Capability type for RPC interfaces (see [L4 : : Cap<T>](#)).*
- class [Varg](#)  
*Variably sized RPC argument.*
- class [Varg\\_list](#)  
*Self-contained list of variable-sized RPC parameters.*
- class [Varg\\_list\\_ref](#)  
*List of variable-sized RPC parameters as received by the server.*
- class [Str\\_cp\\_in](#)  
*Abstraction for extracting a zero-terminated string from an [ipc::Istream](#).*
- class [Msg\\_ptr](#)  
*Pointer to an element of type T in an [ipc::Istream](#).*
- class [Istream](#)  
*Input stream for IPC unmarshalling.*
- class [Ostream](#)  
*Output stream for IPC marshalling.*
- class [Iostream](#)  
*Input/Output stream for IPC [un]marshalling.*

## Typedefs

- typedef unsigned short **Array\_len\_default**  
*Default type for passing length of an array.*

## Functions

- `template<typename T>`  
`Cap< T > make_cap (L4::Cap< T > cap, unsigned rights) noexcept`  
*Make an `L4::lpc::Cap< T >` for the given capability and rights.*
- `template<typename T>`  
`Cap< T > make_cap_rw (L4::Cap< T > cap) noexcept`  
*Make an `L4::lpc::Cap< T >` for the given capability with `L4_CAP_FPAGE_RW` rights.*
- `template<typename T>`  
`Cap< T > make_cap_rws (L4::Cap< T > cap) noexcept`  
*Make an `L4::lpc::Cap< T >` for the given capability with `L4_CAP_FPAGE_RWS` rights.*
- `template<typename T>`  
`Cap< T > make_cap_full (L4::Cap< T > cap) noexcept`  
*Make an `L4::lpc::Cap< T >` for the given capability with full fpage and object-specific rights.*
- `template<typename T>`  
`Internal::Buf_cp_out< T > buf_cp_out (T const *v, unsigned long size)`  
*Insert an array into an `lpc::Ostream`.*
- `template<typename T>`  
`Internal::Buf_cp_in< T > buf_cp_in (T *v, unsigned long &size)`  
*Extract an array from an `lpc::Istream`.*
- `template<typename T>`  
`Str_cp_in< T > str_cp_in (T *v, unsigned long &size)`  
*Create a `Str_cp_in` for the given values.*
- `template<typename T>`  
`Msg_ptr< T > msg_ptr (T *&p)`  
*Create an `Msg_ptr` to adjust the given pointer.*
- `template<typename T>`  
`Internal::Buf_in< T > buf_in (T *&v, unsigned long &size)`  
*Return a pointer to stream array data.*
- `template<typename T>`  
`T read (Istream &s)`  
*Read a value out of a stream.*

## 14.6.1 Detailed Description

IPC related functionality.

## 14.6.2 Function Documentation

### 14.6.2.1 buf\_cp\_in()

```
template<typename T>
Internal::Buf_cp_in< T > L4::Ipc::buf_cp_in (
    T * v,
    unsigned long & size)
```

Extract an array from an `lpc::Istream`.

**Parameters**

	<i>v</i>	Pointer to the array that shall receive the values from the <a href="#">lpc::Istream</a> .
<i>in, out</i>	<i>size</i>	Input: the number of elements the array can take at most Output: the number of elements found in the stream.

[buf\\_cp\\_in\(\)](#) can be used to extract an array from an [lpc::Istream](#). This is the counterpart [buf\\_cp\\_out\(\)](#). The data from the received message is thereby copied to the given buffer and size is set to the number of elements found in the stream. To avoid the copy operation [buf\\_in\(\)](#) may be used instead.

**See also**

[buf\\_in\(\)](#) and [buf\\_cp\\_out\(\)](#).

Definition at line 159 of file [ipc\\_stream](#).

**14.6.2.2 buf\_cp\_out()**

```
template<typename T>
Internal::Buf_cp_out< T > L4::Ipc::buf_cp_out (
    T const * v,
    unsigned long size)
```

Insert an array into an [lpc::Ostream](#).

**Parameters**

<i>v</i>	Pointer to the array that shall be inserted into an <a href="#">lpc::Ostream</a> .
<i>size</i>	Number of elements in the array.

This function inserts an array (e.g. a string) into an [lpc::Ostream](#). The data is copied to the stream. On insertion into the [lpc::Ostream](#) exactly the given number of elements of type T are copied to the message buffer, this means the source buffer is no longer referenced after insertion into the stream.

**See also**

The counterpart is either [buf\\_cp\\_in\(\)](#) or [buf\\_in\(\)](#).

Definition at line 100 of file [ipc\\_stream](#).

### 14.6.2.3 buf\_in()

```
template<typename T>
Internal::Buf_in< T > L4::Ipc::buf_in (
    T *& v,
    unsigned long & size)
```

Return a pointer to stream array data.

#### Parameters

out	<i>v</i>	Pointer to the array within the <a href="#">lpc::lstream</a> .
out	<i>size</i>	The number of elements found in the stream.

This routine provides a possibility to extract an array from an [lpc::lstream](#), without extra copy overhead. In contrast to [buf\\_cp\\_in\(\)](#) the data is not copied to a buffer, but a pointer to the array is returned. The user must make sure the UTCB is not used for other purposes while the returned pointer is still in use.

The mechanism is comparable to that of [Msg\\_ptr](#), however it handles arrays inserted with [buf\\_cp\\_out\(\)](#).

#### See also

[buf\\_cp\\_in\(\)](#) and [buf\\_cp\\_out\(\)](#).

Definition at line 310 of file [ipc\\_stream](#).

### 14.6.2.4 make\_cap()

```
template<typename T>
Cap< T > L4::Ipc::make_cap (
    L4::Cap< T > cap,
    unsigned rights) [noexcept]
```

Make an [L4::lpc::Cap<T>](#) for the given capability and rights.

#### Template Parameters

<i>T</i>	(IMPLICIT) type of the referenced interface
----------	---

#### Parameters


<i>cap</i>	source capability ( <a href="#">L4::Cap&lt;T&gt;</a> )
<i>rights</i>	rights mask that shall be applied on transfer.

Definition at line 785 of file [ipc\\_types](#).

Referenced by [L4virtio::Svr::Driver\\_mem\\_region\\_t< No\\_custom\\_data >::Driver\\_mem\\_region\\_t\(\)](#).



Here is the caller graph for this function:



#### 14.6.2.5 make\_cap\_full()

```

template<typename T>
Cap< T > L4::Ipc::make_cap_full (
    L4::Cap< T > cap) [noexcept]
  
```

Make an L4::IPC::Cap<T> for the given capability with full fpage and object-specific rights.

##### Template Parameters

<i>T</i>	(implicit) type of the referenced interface
----------	---

##### Parameters

<i>cap</i>	source capability ( <a href="#">L4::Cap&lt;T&gt;</a> )
------------	--

##### See also

[L4\\_cap\\_fpage\\_rights](#)

[Attributes and additional permissions for object send items](#)

##### Note

Full rights (including object-specific rights) are required when mapping an IPC gate where the receiver should become the server, i.e. where the receiver wants to call [L4::lpc\\_gate::bind\\_thread\(\)](#) or [L4::lpc\\_gate::bind\\_snd\\_destination\(\)](#).

Definition at line 824 of file [ipc\\_types](#).

References [L4\\_CAP\\_FPAGE\\_RWSD](#), and [L4\\_FPAGE\\_C\\_OBJ\\_RIGHTS](#).

### 14.6.2.6 make\_cap\_rw()

```
template<typename T>
Cap< T > L4::Ipc::make_cap_rw (
    L4::Cap< T > cap) [noexcept]
```

Make an [L4::Ipc::Cap<T>](#) for the given capability with [L4\\_CAP\\_FPAGE\\_RW](#) rights.

#### Template Parameters

<i>T</i>	(IMPLICIT) type of the referenced interface
----------	---

#### Parameters

<i>cap</i>	source capability ( <a href="#">L4::Cap&lt;T&gt;</a> )
------------	--

#### Examples


[examples/libs/l4re/c++/mem\\_alloc/ma+rm.cc](#), [examples/libs/l4re/c++/shared\\_ds/ds\\_clnt.cc](#), and [examples/libs/l4re/c++/shared\\_](#)

Definition at line 795 of file [ipc\\_types](#).

References [L4\\_CAP\\_FPAGE\\_RW](#).

Referenced by [L4Re::Util::Event\\_buffer\\_t< Default\\_event\\_payload >::attach\(\)](#), [L4virtio::Driver::Device::driver\\_connect\(\)](#), [L4Re::Util::Event\\_t< Default\\_event\\_payload >::init\(\)](#), [L4Re::Util::Event\\_t< Default\\_event\\_payload >::init\\_poll\(\)](#), [L4virtio::Driver::Device::register\\_ds\(\)](#), [L4virtio::Driver::Block\\_device::setup\\_device\(\)](#), and [L4virtio::Driver::Virtio\\_net\\_device::setup\\_de](#)

Here is the caller graph for this function:



### 14.6.2.7 make\_cap\_rws()

```
template<typename T>
Cap< T > L4::Ipc::make_cap_rws (
    L4::Cap< T > cap) [noexcept]
```

Make an [L4::ipc::Cap<T>](#) for the given capability with [L4\\_CAP\\_FPAGE\\_RWS](#) rights.

#### Template Parameters

<i>T</i>	(IMPLICIT) type of the referenced interface
----------	---

#### Parameters

<i>cap</i>	source capability ( <a href="#">L4::Cap&lt;T&gt;</a> )
------------	--

Definition at line 805 of file [ipc\\_types](#).

References [L4\\_CAP\\_FPAGE\\_RWS](#).

### 14.6.2.8 msg\_ptr()

```
template<typename T>
Msg_ptr< T > L4::Ipc::msg_ptr (
    T *& p)
```

Create an [Msg\\_ptr](#) to adjust the given pointer.

This function makes it more convenient to extract pointers to data in the message buffer itself from an [ipc::Istream](#). This may be used to avoid copy out of large data structures. (See [Msg\\_ptr](#).)

Definition at line 252 of file [ipc\\_stream](#).

### 14.6.2.9 read()

```
template<typename T>
T L4::Ipc::read (
    Istream & s) [inline]
```

Read a value out of a stream.

#### Parameters

<i>s</i>	An <a href="#">Istream</a> .
----------	------------------------------

#### Returns

The value of type *T*.

The stream position is progressed accordingly.

Definition at line 1289 of file [ipc\\_stream](#).

### 14.6.2.10 str\_cp\_in()

```
template<typename T>
Str_cp_in< T > L4::Ipc::str_cp_in (
    T * v,
    unsigned long & size)
```

Create a [Str\\_cp\\_in](#) for the given values.

#### Parameters

	<i>v</i>	Pointer to the array that shall receive the values from the <a href="#">lpc::lstream</a> .
<i>in, out</i>	<i>size</i>	Input: the number of elements the array can take at most Output: the number of elements found in the stream.

This function makes it more convenient to extract arrays from an [lpc::lstream](#) (

See also

[Str\\_cp\\_in](#).)

Definition at line 213 of file [ipc\\_stream](#).

## 14.7 L4::lpc::Msg Namespace Reference

IPC Message related functionality.

#### Data Structures

- struct [Elem< Array< A, LEN > >](#)  
*Array as input arguments.*
- struct [Elem< Array< A, LEN > & >](#)  
*Array as output argument.*
- struct [Elem< Array\\_ref< A, LEN > & >](#)  
*Array\_ref as output argument.*
- struct [Dir\\_in](#)  
*Marker type for input values.*
- struct [Dir\\_out](#)  
*Marker type for output values.*
- struct [Cls\\_data](#)  
*Marker type for data values.*
- struct [Cls\\_item](#)  
*Marker type for item values.*
- struct [Cls\\_buffer](#)  
*Marker type for receive buffer values.*
- struct [Do\\_in\\_data](#)  
*Marker for Input data.*
- struct [Do\\_out\\_data](#)

- Marker for Output data.*
- struct [Do\\_in\\_items](#)
  - Marker for Input items.*
- struct [Do\\_out\\_items](#)
  - Marker for Output items.*
- struct [Do\\_rcv\\_buffers](#)
  - Marker for receive buffers.*
- struct [Clnt\\_val\\_ops](#)
  - Defines client-side handling of 'MTYPE' as RPC argument.*
- struct [Svr\\_val\\_ops](#)
  - Defines server-side handling for MTYPE server arguments.*
- struct [Is\\_valid\\_rpc\\_type](#)
  - Type trait defining a valid RPC parameter type.*
- struct [Svr\\_arg\\_pack](#)
  - Server-side RPC arguments data structure used to provide arguments to the server-side implementation of an RPC function.*
- struct [True](#)
  - True meta value.*
- struct [False](#)
  - False meta value.*

## Enumerations

- enum {  
[Word\\_bytes](#) = sizeof(l4\_umword\_t) , [Item\\_words](#) = 2 , [Item\\_bytes](#) = Word\_bytes \* Item\_words , [Mr\\_words](#) = L4\_UTCB\_GENERIC\_DATA\_SIZE ,  
[Mr\\_bytes](#) = Word\_bytes \* Mr\_words , [Br\\_bytes](#) = Word\_bytes \* L4\_UTCB\_GENERIC\_BUFFERS\_SIZE }

## Functions

- constexpr unsigned long [align\\_to](#) (unsigned long bytes, unsigned long align) noexcept  
*Pad bytes to the given alignment align (in bytes).*
- template<typename T>  
 constexpr unsigned long [align\\_to](#) (unsigned long bytes) noexcept  
*Pad bytes to the alignment of the type T.*
- template<typename T>  
 constexpr bool [check\\_size](#) (unsigned offset, unsigned limit) noexcept  
*Check if there is enough space for T from offset to limit.*
- template<typename T, typename CTYPE>  
 bool [check\\_size](#) (unsigned offset, unsigned limit, CTYPE cnt) noexcept  
*Check if there is enough space for an array of T from offset to limit.*
- template<typename T>  
 int [msg\\_add](#) (char \*msg, unsigned offs, unsigned limit, T v) noexcept  
*Add some data to a message at offs.*
- template<typename T>  
 int [msg\\_get](#) (char \*msg, unsigned offs, unsigned limit, T &v) noexcept  
*Get some data from a message at offs.*

### 14.7.1 Detailed Description

IPC Message related functionality.

## 14.7.2 Enumeration Type Documentation

### 14.7.2.1 anonymous enum

anonymous enum

#### Enumerator

Word_bytes	number of bytes for one message word
Item_words	number of message words for one message item
Item_bytes	number of bytes for one message item
Mr_words	number of message words available in the UTCB
Mr_bytes	number of bytes available in the UTCB message registers
Br_bytes	number of bytes available in the UTCB buffer registers

Definition at line 85 of file [ipc\\_basics](#).

## 14.7.3 Function Documentation

### 14.7.3.1 align\_to() [1/2]

```
template<typename T>
unsigned long L4::Ipc::Msg::align_to (
    unsigned long bytes) [constexpr, [noexcept]
```

Pad *bytes* to the alignment of the type *T*.

#### Template Parameters

<i>T</i>	The data type used for the alignment
----------	--------------------------------------

#### Parameters

<i>bytes</i>	The value to add the padding to
--------------	---------------------------------

#### Returns

*bytes* padded to achieve the alignment of *T*.

Definition at line 40 of file [ipc\\_basics](#).

References [align\\_to\(\)](#).

Here is the call graph for this function:



### 14.7.3.2 align\_to() [2/2]

```
unsigned long L4::Ipc::Msg::align_to (  
    unsigned long bytes,  
    unsigned long align) [constexpr], [noexcept]
```

Pad bytes to the given alignment *align* (in bytes).

#### Parameters

<i>bytes</i>	The input value in bytes
<i>align</i>	The alignment value in bytes


#### Returns

the result after padding *bytes* to *align*.

Definition at line 30 of file [ipc\\_basics](#).

Referenced by [align\\_to\(\)](#), [msg\\_add\(\)](#), and [msg\\_get\(\)](#).

Here is the caller graph for this function:



### 14.7.3.3 `check_size()` [1/2]

```
template<typename T>
bool L4::Ipc::Msg::check_size (
    unsigned offset,
    unsigned limit) [constexpr], [noexcept]
```

Check if there is enough space for T from offset to limit.

#### Template Parameters

<i>T</i>	The data type that shall be fitted at <i>offset</i>
----------	---

#### Parameters

<i>offset</i>	The current offset in bytes (must already be padded if desired).
<i>limit</i>	The limit in bytes that must not be exceeded after adding the size of <i>T</i> .


#### Returns

true if the limit will not be exceeded, false else.

Definition at line 53 of file [ipc\\_basics](#).

Referenced by [msg\\_add\(\)](#), and [msg\\_get\(\)](#).

Here is the caller graph for this function:



### 14.7.3.4 `check_size()` [2/2]

```
template<typename T, typename CTYPE>
bool L4::Ipc::Msg::check_size (
    unsigned offset,
    unsigned limit,
    CTYPE cnt) [inline], [noexcept]
```

Check if there is enough space for an array of T from offset to limit.



**Template Parameters**

<i>T</i>	The data type that shall be fitted at <i>offset</i>
<i>CTYPE</i>	Type of the <i>cnt</i> parameter

**Parameters**

<i>offset</i>	The current offset in bytes (must already be padded if desired).
<i>limit</i>	The limit in bytes that must not be exceeded after adding <i>cnt</i> times the size of <i>T</i> .
<i>cnt</i>	The number of elements of type <i>T</i> that shall be put at <i>offset</i> .

**Returns**

true if the limit will not be exceeded, false else.

Definition at line 71 of file [ipc\\_basics](#).

References [L4\\_UNLIKELY](#).

**14.7.3.5 msg\_add()**

```
template<typename T>
int L4::IpC::Msg::msg_add (
    char * msg,
    unsigned offs,
    unsigned limit,
    T v) [inline], [noexcept]
```

Add some data to a message at offs.

**Template Parameters**

<i>T</i>	The type of the data to add
----------	-----------------------------

**Parameters**

<i>msg</i>	pointer to the start of the message
<i>offs</i>	The current offset within the message, this shall be padded to the alignment of <i>T</i> if <i>v</i> is added.
<i>limit</i>	The size limit in bytes that offset must not exceed.
<i>v</i>	The value to add to the message


**Returns**

The new offset when successful, a negative value if the given limit will be exceeded.

Definition at line 114 of file [ipc\\_basics](#).

References [align\\_to\(\)](#), [check\\_size\(\)](#), [L4\\_MSGTOOLONG](#), and [L4\\_UNLIKELY](#).

Here is the call graph for this function:

**14.7.3.6 msg\_get()**

```

template<typename T>
int L4::Ipc::Msg::msg_get (
    char * msg,
    unsigned offs,
    unsigned limit,
    T & v) [inline], [noexcept]
  
```

Get some data from a message at offs.

**Template Parameters**

<i>T</i>	The type of the data to read
----------	------------------------------

**Parameters**

<i>msg</i>	Pointer to the start of the message
<i>offs</i>	The current offset within the message, this shall be padded to the alignment of <i>T</i> if a <i>v</i> can be read.
<i>limit</i>	The size limit in bytes that offset must not exceed.
<i>v</i>	A reference to receive the value from the message


**Returns**

The new offset when successful, a negative value if the given limit will be exceeded.

Definition at line 135 of file [ipc\\_basics](#).

References [align\\_to\(\)](#), [check\\_size\(\)](#), [L4\\_EMSGTOOSHORT](#), and [L4\\_UNLIKELY](#).

Here is the call graph for this function:



## 14.8 L4::lpc\_svr Namespace Reference

Helper classes for [L4::Server](#) instantiation.

**Data Structures**

- class [Server\\_iface](#)  
*Interface for server-loop related functions.*
- struct [Ignore\\_errors](#)  
*Mix in for LOOP\_HOOKS to ignore IPC errors.*
- struct [Default\\_timeout](#)  
*Mix in for LOOP\_HOOKS to use a 0 send and a infinite receive timeout.*
- struct [Compound\\_reply](#)  
*Mix in for LOOP\_HOOKS to always use compound reply and wait.*
- struct [Default\\_setup\\_wait](#)  
*Mix in for LOOP\_HOOKS for setup\_wait no op.*
- struct [Direct\\_dispatch](#)  
*Direct dispatch helper, for forwarding dispatch calls to a registry R.*
- struct [Direct\\_dispatch< R \\* >](#)  
*Direct dispatch helper, for forwarding dispatch calls via a pointer to a registry R.*
- struct [Exc\\_dispatch](#)  
*Dispatch helper wrapping try {} catch {} around the dispatch call.*
- struct [Dbg\\_dispatch](#)  
*Dispatch helper that, in addition to what [Exc\\_dispatch](#) does, prints exception messages.*
- class [Br\\_manager\\_no\\_buffers](#)  
*Empty implementation of [Server\\_iface](#).*
- struct [Default\\_loop\\_hooks](#)  
*Default LOOP\_HOOKS.*
- class [Timeout](#)  
*Callback interface for [Timeout\\_queue](#).*
- class [Timeout\\_queue](#)  
*[Timeout](#) queue to be used in l4re server loop.*
- class [Timeout\\_queue\\_hooks](#)  
*Loop hooks mixin for integrating a timeout queue into the server loop.*

## Enumerations

- enum [Reply\\_mode](#) { [Reply\\_compound](#) , [Reply\\_separate](#) }  
*Reply mode for server loop.*

### 14.8.1 Detailed Description

Helper classes for [L4::Server](#) instantiation.

## 14.9 L4::Typeid Namespace Reference

Definition of interface data-type helpers.

### Data Structures

- struct [P\\_dispatch](#)  
*Use for protocol based dispatch stage.*
- struct [Raw\\_ipc](#)  
*RPCs list for passing raw incoming IPC to the server object.*
- struct [Rpc](#)  
*Standard list of RPCs of an interface.*
- struct [Rpc\\_code](#)  
*List of RPCs of an interface using a special opcode type.*
- struct [Rpc\\_nocode](#)  
*List of RPCs of an interface using a single operation without an opcode.*
- struct [Rpc\\_sys](#)  
*List of RPCs typically used for kernel interfaces.*

### 14.9.1 Detailed Description

Definition of interface data-type helpers.

#### Note

These type helpers are intended for internal use, if you look for standard C++ type traits use the `<type_traits>` header for the standard C++ library or use `<l4/cxx/type_traits>`.

## 14.10 L4::Types Namespace Reference

[L4](#) basic type helpers for C++.

## Data Structures

- class [Flags](#)  
*Template for defining typical [Flags](#) bitmaps.*
- struct [Int\\_for\\_size](#)  
*Metafunction to get an unsigned integral type for the given size.*
- struct [Int\\_for\\_type](#)  
*Metafunction to get an integral type of the same size as  $T$ .*
- struct [Flags\\_ops\\_t](#)  
*Mixin class to define a set of friend bitwise operators on  $DT$ .*
- struct [Flags\\_t](#)  
*Template type to define a flags type with bitwise operations.*
- struct [\\_\\_Add\\_rvalue\\_reference\\_helper](#)  
*Helper template for [Add\\_rvalue\\_reference](#).*
- struct [\\_\\_Add\\_rvalue\\_reference\\_helper](#)<  $T$ ,  $\text{Void}< T \&\& >$  >  
*Helper template for [Add\\_rvalue\\_reference](#).*
- struct [Add\\_rvalue\\_reference](#)  
*Create an rvalue reference of the given type.*
- struct [Bool](#)  
*Boolean meta type.*
- struct [False](#)  
*[False](#) meta value.*
- struct [True](#)  
*[True](#) meta value.*
- struct [Integral\\_constant](#)  
*Wrapper for a static constant of the given type.*
- struct [Is\\_enum](#)  
*Check whether the given type is an enumeration type.*
- struct [\\_\\_Underlying\\_type\\_helper](#)  
*Helper template for [Underlying\\_type](#).*
- struct [\\_\\_Underlying\\_type\\_helper](#)<  $T$ ,  $\text{false}$  >  
*Helper template for [Underlying\\_type](#).*
- struct [Underlying\\_type](#)  
*Get an underlying type of an enumeration type.*
- struct [Same](#)  
*Compare two data types for equality.*

## Typedefs

- `template<typename...>`  
`using Void = void`  
*Map a sequence of any types to the void type.*
- `template<typename T>`  
`using Add_rvalue_reference_t = typename Add\_rvalue\_reference< $T$ >::type`  
*Helper type for the [Add\\_rvalue\\_reference](#).*
- `template<typename T>`  
`using Underlying_type_t = typename Underlying\_type< $T$ >::type`  
*Helper type for [Underlying\\_type](#).*
- `template<bool Condition, typename T = void>`  
`using Enable_if_t = typename Enable\_if< $\text{Condition}$ ,  $T$ >::type`  
*Helper type for [Enable\\_if](#).*

## Functions

- `template<typename T>`  
`Add_rvalue_reference_t< T > declval () noexcept`  
*Template for writing typed expressions in unevaluated contexts.*

### 14.10.1 Detailed Description

[L4](#) basic type helpers for C++.

### 14.10.2 Function Documentation

#### 14.10.2.1 declval()

```
template<typename T>
Add_rvalue_reference_t< T > L4::Types::declval () [noexcept]
```

Template for writing typed expressions in unevaluated contexts.

In unevaluated contexts, the template converts a type (possibly an incomplete type) to an expression of that type.

#### Template Parameters

<i>T</i>	Type to be converted to an expression of that type.
----------	---

## 14.11 L4Re Namespace Reference

[L4Re](#) C++ Interfaces.

## Namespaces

- namespace [Vfs](#)  
*Virtual file system for interfaces in POSIX libc.*
- namespace [Util](#)  
*Documentation of the [L4](#) Runtime Environment utility functionality in C++.*

## Data Structures

- class [Cap\\_alloc](#)  
*Capability allocator interface.*
- class [Smart\\_cap\\_auto](#)  
*Helper for [Unique\\_cap](#) and [Unique\\_del\\_cap](#).*
- class [Smart\\_count\\_cap](#)  
*Helper for [Ref\\_cap](#) and [Ref\\_del\\_cap](#).*
- class [Console](#)  
*[Console](#) class.*
- class [Dataspace](#)  
*Interface for memory-like objects.*
- class [Debug\\_obj](#)  
*Debug interface.*
- class [Dma\\_space](#)  
*Managed DMA Address Space.*
- class [Env](#)  
*C++ interface of the initial environment that is provided to an [L4](#) task.*
- class [Event](#)  
*[Event](#) class.*
- struct [Default\\_event\\_payload](#)  
*Default event stream payload.*
- class [Event\\_buffer\\_t](#)  
*[Event](#) buffer class.*
- class [Inhibitor](#)  
*Set of inhibitor locks, which inhibit specific actions when held.*
- class [Itas](#)  
*Interface to the ITAS.*
- class [Log](#)  
*[Log](#) interface class.*
- class [Mem\\_alloc](#)  
*Memory allocation interface.*
- struct [Mmio\\_space](#)  
*Interface for memory-like address space accessible via IPC.*
- class [Namespace](#)  
*Name-space interface.*
- class [Parent](#)  
*[Parent](#) interface.*
- struct [Random](#)  
*Low-bandwidth interface for random number generators.*
- class [Rm](#)  
*[Region](#) map.*

## Typedefs

- `template<typename T>`  
using [Shared\\_cap](#) = `L4::Detail::Shared_cap_impl<T, L4Re::Smart\_count\_cap<L4\_FP\_ALL\_SPACES>>`  
*Shared capability that implements automatic free and unmap of the capability selector.*
- `template<typename T>`  
using [Shared\\_del\\_cap](#) = `L4::Detail::Shared_cap_impl<T, L4Re::Smart\_count\_cap<L4\_FP\_DELETE\_OBJ>>`  
*Shared capability that implements automatic free and unmap+delete of the capability selector.*

- `template<typename T>`  
`using Unique_cap = L4::Detail::Unique_cap_impl<T, L4Re::Smart_cap_auto<L4_FP_ALL_SPACES>>`  
*Unique capability that implements automatic free and unmap of the capability selector.*
- `template<typename T>`  
`using Unique_del_cap = L4::Detail::Unique_cap_impl<T, L4Re::Smart_cap_auto<L4_FP_DELETE_OBJ>>`  
*Unique capability that implements automatic free and unmap+delete of the capability selector.*

## Functions

- `void throw_error (long err, char const *extra="")`  
*Generate C++ exception.*
- `l4_ret_t chksys (l4_ret_t err, char const *extra="", l4_ret_t ret=0)`  
*Generate C++ exception on error.*
- `l4_ret_t chksys (l4_msgtag_t const &t, char const *extra="", l4_utcb_t *utcb=l4_utcb(), l4_ret_t ret=0)`  
*Generate C++ exception on error.*
- `l4_ret_t chksys (l4_msgtag_t const &t, l4_utcb_t *utcb, char const *extra="")`  
*Generate C++ exception on error.*
- `template<typename T>`  
`T chkcap (T &&cap, char const *extra="", l4_ret_t err=-L4_ENOMEM)`  
*Check for valid capability or raise C++ exception.*
- `l4_msgtag_t chkipc (l4_msgtag_t tag, char const *extra="", l4_utcb_t *utcb=l4_utcb())`  
*Test a message tag for IPC errors.*
- `template<typename T>`  
`Shared_cap< T > make_shared_cap (L4Re::Cap_alloc *ca)`  
*Allocate a capability slot and wrap it in a Shared\_cap.*
- `template<typename T>`  
`Shared_del_cap< T > make_shared_del_cap (L4Re::Cap_alloc *ca)`  
*Allocate a capability slot and wrap it in a Shared\_del\_cap.*
- `template<typename T>`  
`Unique_cap< T > make_unique_cap (L4Re::Cap_alloc *ca)`  
*Allocate a capability slot and wrap it in an Unique\_cap.*
- `template<typename T>`  
`Unique_del_cap< T > make_unique_del_cap (L4Re::Cap_alloc *ca)`  
*Allocate a capability slot and wrap it in an Unique\_del\_cap.*

### 14.11.1 Detailed Description

[L4Re C++ Interfaces.](#)

[L4 Runtime Environment.](#)



## 14.11.2 Typedef Documentation

### 14.11.2.1 Shared\_cap

```
template<typename T>
using L4Re::Shared_cap = L4::Detail::Shared_cap_impl<T, L4Re::Smart_count_cap<L4_FP_ALL_SPACES>>
```

Shared capability that implements automatic free and unmap of the capability selector.

#### Template Parameters

<i>T</i>	Type of the object the capability refers to.
----------	--

This shared capability implements a counted reference to a capability selector. The capability shall be unmapped and freed when the reference count in the allocator goes to zero.

#### Note

This type is intended for users who implement a custom capability allocator; otherwise use [L4Re::Util::Shared\\_cap](#).

Definition at line 33 of file [shared\\_cap](#).

### 14.11.2.2 Shared\_del\_cap

```
template<typename T>
using L4Re::Shared_del_cap = L4::Detail::Shared_cap_impl<T, L4Re::Smart_count_cap<L4_FP_DELETE_OBJ>>
```

Shared capability that implements automatic free and unmap+delete of the capability selector.

#### Template Parameters

<i>T</i>	Type of the object the capability refers to.
----------	--

This shared capability implements a counted reference to a capability selector. The capability shall be unmapped and freed when the reference count in the allocator goes to zero. The main difference to [Shared\\_cap](#) is that the unmap is done with the deletion flag enabled and this leads to the deletion of the object if the current task holds appropriate deletion rights.

#### Note

This type is intended for users who implement a custom capability allocator; otherwise use [L4Re::Util::Shared\\_del\\_cap](#).

Definition at line 70 of file [shared\\_cap](#).

### 14.11.2.3 Unique\_cap

```
template<typename T>
using L4Re::Unique_cap = L4::Detail::Unique_cap_impl<T, L4Re::Smart_cap_auto<L4_FP_ALL_SPACES>>
```

Unique capability that implements automatic free and unmap of the capability selector.

#### Template Parameters

<i>T</i>	Type of the object the capability refers to.
----------	--

The ownership of the capability is managed in the same way as `unique_ptr`.

#### Note

This type is intended for users who implement a custom capability allocator; otherwise use `L4Re::Util::Unique_cap`.

Definition at line 31 of file `unique_cap`.

### 14.11.2.4 Unique\_del\_cap

```
template<typename T>
using L4Re::Unique_del_cap = L4::Detail::Unique_cap_impl<T, L4Re::Smart_cap_auto<L4_FP_DELETE_OBJ>>
```

Unique capability that implements automatic free and unmap+delete of the capability selector.

#### Template Parameters

<i>T</i>	Type of the object the capability refers to.
----------	--

The main difference to `Unique_cap` is that the unmap is done with the deletion flag enabled and this leads to the deletion of the object if the current task holds appropriate deletion rights.

#### Note

This type is intended for users who implement a custom capability allocator; otherwise use `L4Re::Util::Unique_del_cap`.

Definition at line 65 of file `unique_cap`.

### 14.11.3 Function Documentation

#### 14.11.3.1 chkcap()

```
template<typename T>
T L4Re::chkcap (
    T && cap,
    char const * extra = "",
    l4_ret_t err = -L4_ENOMEM) [inline]
```

Check for valid capability or raise C++ exception.

#### Template Parameters

<i>T</i>	Type of object to check, must be capability-like ( <a href="#">L4::Cap</a> , <a href="#">L4Re::Util::Unique_cap</a> etc.)
----------	---

#### Parameters

<i>cap</i>	Capability value to check.
<i>extra</i>	Optional text for exception.
<i>err</i>	Error value for exception or 0 if the error code stored in the invalid capability should be used.

This function checks whether the capability is valid. If the capability is invalid, a C++ exception is generated, using *err* if *err* is not zero, otherwise the capability value is used. A valid capability will just be returned.

Definition at line 149 of file [error\\_helper](#).


References [L4\\_ENOMEM](#), [L4\\_UNLIKELY](#), and [throw\\_error\(\)](#).

Referenced by [L4virtio::Svr::Dev\\_config::Dev\\_config\(\)](#), [L4virtio::Driver::Device::driver\\_connect\(\)](#), [L4virtio::Svr::Console::Device::register\\_single\\_driver\\_irq\(\)](#), [L4virtio::Svr::Virtio\\_gpio< Request\\_handler, Epiface >::register\\_single\\_driver\\_irq\(\)](#), [L4virtio::Svr::Virtio\\_i2c< Request\\_handler, Epiface >::register\\_single\\_driver\\_irq\(\)](#), [L4virtio::Svr::Virtio\\_rng< Rnd\\_state, Epiface >::register\\_single\\_driver\\_irq\(\)](#), [L4virtio::Svr::Virtio\\_spi< Spi\\_request\\_handler, Epiface >::register\\_single\\_driver\\_irq\(\)](#), [L4virtio::Driver::Block\\_device::setup\\_device\(\)](#), and [L4virtio::Driver::Virtio\\_net\\_device::setup\\_device\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 14.11.3.2 chkipc()

```

14_msgtag_t L4Re::chkipc (
    14_msgtag_t tag,
    char const * extra = "",
    14_utcb_t * utcb = 14_utcb()) [inline]

```

Test a message tag for IPC errors.

#### Parameters

<i>tag</i>	Message tag returned by the IPC.
<i>extra</i>	Exception message in case of error.
<i>utcb</i>	The UTCB used in the IPC operation.

**Returns**

On IPC error an exception is thrown, otherwise `tag` is returned.

**Exceptions**

<code>L4::Runtime_exception</code>	with the translated IPC error code
------------------------------------	------------------------------------

This function does not check the message tag's label value.


**Note**

This must be called on a message tag before the UTCB is changed.

Definition at line 180 of file [error\\_helper](#).

References [chksys\(\)](#), [l4\\_msgtag\\_t::has\\_error\(\)](#), and [L4\\_UNLIKELY](#).

Here is the call graph for this function:

**14.11.3.3 chksys() [1/3]**

```

l4_ret_t L4Re::chksys (
    l4_msgtag_t const & t,
    char const * extra = "",
    l4_utcb_t * utcb = l4_utcb(),
    l4_ret_t ret = 0) [inline]
  
```

Generate C++ exception on error.

**Parameters**


<code>t</code>	Message tag.
<code>extra</code>	Optional text for exception (default "")
<code>utcb</code>	Option UTCB
<code>ret</code>	Optional value for exception, default is error value (err)

This function throws an exception if the message tag contains an error or the label in the message tag is negative. Otherwise the label in the message tag is returned.

Definition at line 93 of file [error\\_helper](#).

References [l4\\_msgtag\\_t::has\\_error\(\)](#), [L4\\_UNLIKELY](#), [l4\\_msgtag\\_t::label\(\)](#), and [throw\\_error\(\)](#).

Here is the call graph for this function:



#### 14.11.3.4 `chksys()` [2/3]

```

l4_ret_t L4Re::chksys (
    l4_msgtag_t const & t,
    l4_utcb_t * utcb,
    char const * extra = "") [inline]

```

Generate C++ exception on error.

##### Parameters


<i>t</i>	Message tag.
<i>utcb</i>	UTCB.
<i>extra</i>	Optional text for exception (default "")

This function throws an exception if the message tag contains an error or the label in the message tag is negative. Otherwise the label in the message tag is returned.

Definition at line 116 of file [error\\_helper](#).

References [chksys\(\)](#).

Here is the call graph for this function:



14.11.3.5 `chksys()` [3/3]

```

l4_ret_t L4Re::chksys (
    l4_ret_t err,
    char const * extra = "",
    l4_ret_t ret = 0) [inline]

```

Generate C++ exception on error.

**Parameters**

<i>err</i>	Error value, if negative exception will be thrown
<i>extra</i>	Optional text for exception (default "")
<i>ret</i>	Optional value for exception, default is error value (err)

This function throws an exception if the `err` is negative and otherwise returns `err`.

**Examples**

[examples/libs/l4re/c++/shared\\_ds/ds\\_srv.cc](#).

Definition at line 72 of file [error\\_helper](#).


References [L4\\_UNLIKELY](#), and [throw\\_error\(\)](#).

Referenced by [L4virtio::Svr::Driver\\_mem\\_list\\_t< No\\_custom\\_data >::add\(\)](#), [chkipc\(\)](#), [chksys\(\)](#), [L4virtio::Svr::Dev\\_config::Dev\\_config\(\)](#), [L4virtio::Svr::Device\\_t< No\\_custom\\_data >::device\\_notify\\_irq\(\)](#), [L4virtio::Svr::Device\\_t< No\\_custom\\_data >::device\\_notify\\_irq\(\)](#), [L4virtio::Driver::Device::driver\\_acknowledge\(\)](#), [L4virtio::Driver::Device::driver\\_connect\(\)](#), [L4virtio::Svr::Driver\\_mem\\_region\\_t< No\\_custom\\_data >::register\\_driver\\_irq\(\)](#), [L4virtio::Driver::Block\\_device::process\\_used\\_queue\(\)](#), [L4virtio::Svr::Device\\_t< No\\_custom\\_data >::register\\_driver\\_irq\(\)](#), [L4virtio::Svr::Console::Device::register\\_single\\_driver\\_irq\(\)](#), [L4virtio::Svr::Device\\_t< No\\_custom\\_data >::register\\_single\\_driver\\_irq\(\)](#), [L4virtio::Svr::Virtio\\_gpio< Request\\_handler, Epiface >::register\\_single\\_driver\\_irq\(\)](#), [L4virtio::Svr::Virtio\\_i2c< Request\\_handler, Epiface >::register\\_single\\_driver\\_irq\(\)](#), [L4virtio::Svr::Virtio\\_rng< Rnd\\_state, Epiface >::register\\_single\\_driver\\_irq\(\)](#), [L4virtio::Svr::Virtio\\_spi< Spi\\_request\\_handler, Epiface >::register\\_single\\_driver\\_irq\(\)](#), [L4virtio::Svr::Virtio\\_net::register\\_single\\_driver\\_irq\(\)](#), [L4virtio::Svr::Driver\\_mem\\_list\\_t< No\\_custom\\_data >::remove\(\)](#), [L4virtio::Driver::Block\\_device::process\\_used\\_queue\(\)](#), [L4virtio::Driver::Virtio\\_net\\_device::setup\\_device\(\)](#), [L4virtio::Svr::Console::Virtio\\_con::Virtio\\_con\(\)](#), and [L4virtio::Driver::Virtio\\_net\\_device::setup\\_device\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 14.11.3.6 make\_shared\_cap()

```

template<typename T>
Shared_cap< T > L4Re::make_shared_cap (
    L4Re::Cap_alloc * ca)

```



Allocate a capability slot and wrap it in a [Shared\\_cap](#).

#### Template Parameters

<i>T</i>	Type of the object the capability refers to.
----------	--

#### Parameters

<i>ca</i>	Capability allocator to use.
-----------	------------------------------

#### Note

This function is intended for users who implement a custom capability allocator; otherwise use [L4Re::Util::make\\_shared\\_cap<T>\(\)](#).

Definition at line 50 of file [shared\\_cap](#).

References [L4Re::Cap\\_alloc::alloc\(\)](#).

Here is the call graph for this function:



#### 14.11.3.7 make\_shared\_del\_cap()

```

template<typename T>
Shared\_del\_cap< T > L4Re::make_shared_del_cap (
    L4Re::Cap\_alloc * ca)
  
```

Allocate a capability slot and wrap it in a [Shared\\_del\\_cap](#).

#### Template Parameters

<i>T</i>	Type of the object the capability refers to.
----------	--

#### Parameters

<i>ca</i>	Capability allocator to use.
-----------	------------------------------

**Note**

This function is intended for users who implement a custom capability allocator; otherwise use [L4Re::Util::make\\_shared\\_del\\_cap<T>\(\)](#).

Definition at line 87 of file [shared\\_cap](#).

References [L4Re::Cap\\_alloc::alloc\(\)](#).

Here is the call graph for this function:

**14.11.3.8 make\_unique\_cap()**

```

template<typename T>
Unique_cap< T > L4Re::make_unique_cap (
    L4Re::Cap_alloc * ca)
  
```

Allocate a capability slot and wrap it in an [Unique\\_cap](#).

**Template Parameters**

<i>T</i>	Type of the object the capability refers to.
----------	--

**Parameters**

<i>ca</i>	Capability allocator to use.
-----------	------------------------------

**Note**

This function is intended for users who implement a custom capability allocator; otherwise use [L4Re::Util::make\\_unique\\_cap<T>\(\)](#).

Definition at line 48 of file [unique\\_cap](#).

References [L4Re::Cap\\_alloc::alloc\(\)](#).

Here is the call graph for this function:



### 14.11.3.9 make\_unique\_del\_cap()

```
template<typename T>
Unique_del_cap< T > L4Re::make_unique_del_cap (
    L4Re::Cap_alloc * ca)
```

Allocate a capability slot and wrap it in an [Unique\\_del\\_cap](#).

#### Template Parameters

<i>T</i>	Type of the object the capability refers to.
----------	--

#### Parameters

<i>ca</i>	Capability allocator to use.
-----------	------------------------------

#### Note

This function is intended for users who implement a custom capability allocator; otherwise use [L4Re::Util::make\\_unique\\_del\\_cap<T>\(\)](#).

Definition at line 82 of file [unique\\_cap](#).

References [L4Re::Cap\\_alloc::alloc\(\)](#).

Here is the call graph for this function:



### 14.11.3.10 throw\_error()

```
void L4Re::throw_error (
    long err,
    char const * extra = "") [inline]
```

Generate C++ exception.

#### Parameters

<i>err</i>	Error value
------------	-------------

<i>extra</i>	Optional text for exception (default "")
--------------	--

This function throws an [L4](#) exception. The exact exception type depends on the error value (err). This function does never return.

#### Examples


[examples/libs/l4re/c++/shared\\_ds/ds\\_srv.cc](#).

Definition at line 37 of file [error\\_helper](#).

References [L4\\_EEXIST](#), [L4\\_ENOENT](#), [L4\\_ENOMEM](#), and [L4\\_ERANGE](#).

Referenced by [chkcap\(\)](#), [chksys\(\)](#), [chksys\(\)](#), and [L4virtio::Svr::Virtio\\_spi< Spi\\_request\\_handler, Epiface >::Request\\_processor::get\\_](#)

Here is the caller graph for this function:



## 14.12 L4Re::Util Namespace Reference

Documentation of the [L4](#) Runtime Environment utility functionality in C++.

## Data Structures

- class [Cap\\_alloc\\_base](#)  
*Capability allocator.*
- class [Br\\_manager](#)  
*Buffer-register (BR) manager for [L4::Server](#).*
- struct [Br\\_manager\\_hooks](#)  
*Predefined server-loop hooks for a server loop using the [Br\\_manager](#).*
- struct [Br\\_manager\\_timeout\\_hooks](#)  
*Predefined server-loop hooks for a server with using the [Br\\_manager](#) and a timeout queue.*
- class [Smart\\_cap\\_auto](#)  
*Helper for [Unique\\_cap](#) and [Unique\\_del\\_cap](#).*
- class [Smart\\_count\\_cap](#)  
*Helper for [Ref\\_cap](#) and [Ref\\_del\\_cap](#).*
- struct [Ref\\_cap](#)  
*Automatic capability that implements automatic free and unmap of the capability selector.*
- struct [Ref\\_del\\_cap](#)  
*Automatic capability that implements automatic free and unmap+delete of the capability selector.*
- class [\\_Cap\\_alloc](#)  
*Adapter to expose the cap allocator implementation as [L4Re::Cap\\_alloc](#) compatible class.*
- struct [Counter](#)  
*Counter for [Counting\\_cap\\_alloc](#) with variable data width.*
- struct [Counter\\_atomic](#)  
*Thread safe version of counter for [Counting\\_cap\\_alloc](#).*
- class [Counting\\_cap\\_alloc](#)  
*Internal reference-counting cap allocator.*
- class [Dataspace\\_svr](#)  
*[Dataspace](#) server class.*
- class [Event\\_t](#)  
*Convenience wrapper for getting access to an event object.*
- class [Event\\_buffer\\_t](#)  
*Event\_buffer utility class.*
- class [Event\\_buffer\\_consumer\\_t](#)  
*An event buffer consumer.*
- class [Event\\_svr](#)  
*Convenience wrapper for implementing an event server.*
- class [Item\\_alloc\\_base](#)  
*Item allocator.*
- class [Object\\_registry](#)  
*A registry that manages server objects and their attached IPC gates for a single server loop for a specific thread.*
- class [Registry\\_server](#)  
*A server loop object which has a [Object\\_registry](#) included.*
- class [Vcon\\_svr](#)  
*[Console](#) server template class.*
- class [Bitmap\\_base](#)  
*Basic bitmap abstraction.*
- class [Bitmap](#)  
*A static bitmap.*

## Typedefs

- `template<typename T>`  
using `Shared_cap` = `L4::Detail::Shared_cap_impl<T, L4Re::Util::Smart_count_cap<L4_FP_ALL_SPACES>>`  
*Shared capability that implements automatic free and unmap of the capability selector.*
- `template<typename T>`  
using `Shared_del_cap` = `L4::Detail::Shared_cap_impl<T, L4Re::Util::Smart_count_cap<L4_FP_DELETE_OBJ>>`  
*Shared capability that implements automatic free and unmap+delete of the capability selector.*
- `template<typename T>`  
using `Unique_cap` = `L4::Detail::Unique_cap_impl<T, L4Re::Util::Smart_cap_auto<L4_FP_ALL_SPACES>>`  
*Unique capability that implements automatic free and unmap of the capability selector.*
- `template<typename T>`  
using `Unique_del_cap` = `L4::Detail::Unique_cap_impl<T, L4Re::Util::Smart_cap_auto<L4_FP_DELETE_OBJ>>`  
*Unique capability that implements automatic free and unmap+delete of the capability selector.*

## Functions

- `template<typename T>`  
`Ref_cap< T >::Cap make_ref_cap ()`  
*Allocate a capability slot and wrap it in a `Ref_cap`.*
- `template<typename T>`  
`Ref_del_cap< T >::Cap make_ref_del_cap ()`  
*Allocate a capability slot and wrap it in a `Ref_del_cap`.*
- `int kumem_alloc (l4_addr_t *mem, unsigned pages_order, L4::Cap< L4::Task > task=L4Re::Env::env() ->task(), L4::Cap< L4Re::Rm > rm=L4Re::Env::env() ->rm()) noexcept`  
*Allocate state area.*
- `template<typename T>`  
`Shared_cap< T > make_shared_cap ()`  
*Allocate a capability slot and wrap it in a `Shared_cap`.*
- `template<typename T>`  
`Shared_del_cap< T > make_shared_del_cap ()`  
*Allocate a capability slot and wrap it in a `Shared_del_cap`.*
- `template<typename T>`  
`Unique_cap< T > make_unique_cap ()`  
*Allocate a capability slot and wrap it in an `Unique_cap`.*
- `template<typename T>`  
`Unique_del_cap< T > make_unique_del_cap ()`  
*Allocate a capability slot and wrap it in an `Unique_del_cap`.*

## Variables

- `_Cap_alloc cap_alloc`  
*Capability allocator.*

### 14.12.1 Detailed Description

Documentation of the [L4](#) Runtime Environment utility functionality in C++.

## 14.12.2 Typedef Documentation

### 14.12.2.1 Shared\_cap

```
template<typename T>
```

```
using L4Re::Util::Shared_cap = L4::Detail::Shared_cap_impl<T, L4Re::Util::Smart_count_cap<L4_FP_ALL_SPACES>>
```

Shared capability that implements automatic free and unmap of the capability selector.

#### Template Parameters

<i>T</i>	Type of the object the capability refers to.
----------	--

This shared capability implements a counted reference to a capability selector. The capability shall be unmapped and freed when the reference count in the allocator goes to zero.

Usage:

```
L4Re::Util::Shared_cap<L4Re::Dataspace> global_ds_cap;

{
    L4Re::Util::Shared_cap<L4Re::Dataspace>
        ds_cap = make_shared_cap<L4Re::Dataspace>();
    // reference count for the allocated cap selector is now 1

    // use the dataspace cap
    L4Re::chksys(mem_alloc->alloc(4096, ds_cap.get()));

    global_ds_cap = ds_cap;
    // reference count is now 2
    ...
}
// reference count dropped to 1 (ds_cap is no longer existing).
```

Definition at line 48 of file [shared\\_cap](#).

### 14.12.2.2 Shared\_del\_cap

```
template<typename T>
```

```
using L4Re::Util::Shared_del_cap = L4::Detail::Shared_cap_impl<T, L4Re::Util::Smart_count_cap<L4_FP_DELETE_OB
```

Shared capability that implements automatic free and unmap+delete of the capability selector.

#### Template Parameters

<i>T</i>	Type of the object the capability refers to.
----------	--

This shared capability implements a counted reference to a capability selector. The capability shall be unmapped and freed when the reference count in the allocator goes to zero. The main difference to [Shared\\_cap](#) is that the unmap is done with the deletion flag enabled and this leads to the deletion of the object if the current task holds appropriate deletion rights.

Usage:



```

L4Re::Util::Shared_del_cap<L4Re::Dataspace> global_ds_cap;

{
    L4Re::Util::Shared_del_cap<L4Re::Dataspace>
        ds_cap = make_shared_del_cap<L4Re::Dataspace>();
    // reference count for the allocated cap selector is now 1

    // use the dataspace cap
    L4Re::chksys(mem_alloc->alloc(4096, ds_cap.get()));

    global_ds_cap = ds_cap;
    // reference count is now 2
    ...
}
// reference count dropped to 1 (ds_cap is no longer existing).
...
global_ds_cap = L4_INVALID_CAP;
// reference count dropped to 0 (data space shall be deleted).

```

Definition at line 99 of file [shared\\_cap](#).

### 14.12.2.3 Unique\_cap

```

template<typename T>
using L4Re::Util::Unique_cap = L4::Detail::Unique_cap_impl<T, L4Re::Util::Smart_cap_auto<L4_FP_ALL_SPACES>>

```

Unique capability that implements automatic free and unmap of the capability selector.

#### Template Parameters

<i>T</i>	Type of the object the capability refers to.
----------	--

The ownership of the capability is managed in the same way as `unique_ptr`.

Usage:

```

{
    L4Re::Util::Unique_cap<L4Re::Dataspace>
        ds_cap = L4Re::Util::make_unique_cap<L4Re::Dataspace>();

    // use the dataspace cap
    L4Re::chksys(mem_alloc->alloc(L4_PAGESIZE, ds_cap.get()));

    ...

    // At the end of the scope ds_cap is unmapped and the capability
    // selector is freed.
}

```

Definition at line 43 of file [unique\\_cap](#).

#### 14.12.2.4 Unique\_del\_cap

```
template<typename T>
using L4Re::Util::Unique_del_cap = L4::Detail::Unique_cap_impl<T, L4Re::Util::Smart_cap_auto<L4_FP_DELETE_OBJ
```

Unique capability that implements automatic free and unmap+delete of the capability selector.

##### Template Parameters

<i>T</i>	Type of the object the capability refers to.
----------	--

The main difference to [Unique\\_cap](#) is that the unmap is done with the deletion flag enabled and this leads to the deletion of the object if the current task holds appropriate deletion rights.

Usage:

```
{
    L4Re::Util::Unique_del_cap<L4Re::Dataspace>
        ds_cap = make_unique_del_cap<L4Re::Dataspace>();

    // use the dataspace cap
    L4Re::chksys(mem_alloc->alloc(L4_PAGESIZE, ds_cap.get()));

    ...

    // At the end of the scope ds_cap is unmapped and the capability
    // selector is freed. Because the deletion flag is set the data space
    // shall also be deleted (even if there are other references to this
    // data space).
}
```

Definition at line 87 of file [unique\\_cap](#).

### 14.12.3 Function Documentation

#### 14.12.3.1 make\_shared\_cap()

```
template<typename T>
Shared_cap< T > L4Re::Util::make_shared_cap ()
```

Allocate a capability slot and wrap it in a [Shared\\_cap](#).

##### Template Parameters


<i>T</i>	Type of the object the capability refers to.
----------	--

Definition at line 61 of file [shared\\_cap](#).

References [cap\\_alloc](#).

Referenced by [L4virtio::Svr::Dev\\_config::Dev\\_config\(\)](#).

Here is the caller graph for this function:



### 14.12.3.2 make\_shared\_del\_cap()

```
template<typename T>
Shared_del_cap< T > L4Re::Util::make_shared_del_cap ()
```

Allocate a capability slot and wrap it in a [Shared\\_del\\_cap](#).

#### Template Parameters

<i>T</i>	Type of the object the capability refers to.
----------	--

Definition at line 112 of file [shared\\_cap](#).

References [cap\\_alloc](#).

### 14.12.3.3 make\_unique\_cap()

```
template<typename T>
Unique_cap< T > L4Re::Util::make_unique_cap ()
```

Allocate a capability slot and wrap it in an [Unique\\_cap](#).

#### Template Parameters


<i>T</i>	Type of the object the capability refers to.
----------	--

Definition at line 56 of file [unique\\_cap](#).

References [cap\\_alloc](#).

Referenced by [L4virtio::Driver::Device::driver\\_connect\(\)](#), [L4virtio::Driver::Block\\_device::setup\\_device\(\)](#), and [L4virtio::Driver::Virtio\\_net\\_device::setup\\_device\(\)](#).

Here is the caller graph for this function:



#### 14.12.3.4 make\_unique\_del\_cap()

```
template<typename T>
Unique_del_cap< T > L4Re::Util::make_unique_del_cap ()
```

Allocate a capability slot and wrap it in an [Unique\\_del\\_cap](#).

##### Template Parameters

<i>T</i>	Type of the object the capability refers to.
----------	--

Definition at line 100 of file [unique\\_cap](#).

References [cap\\_alloc](#).

### 14.13 L4Re::Vfs Namespace Reference

Virtual file system for interfaces in POSIX libc.

#### Data Structures

- class [Be\\_file](#)  
*Boiler plate class for implementing an open file for L4Re::Vfs.*
- class [Be\\_file\\_system](#)  
*Boilerplate class for implementing a L4Re::Vfs::File\_system.*
- class [Generic\\_file](#)  
*The common interface for an open POSIX file.*
- class [Directory](#)  
*Interface for a POSIX file that is a directory.*
- class [Regular\\_file](#)  
*Interface for a POSIX file that provides regular file semantics.*
- class [Special\\_file](#)  
*Interface for a POSIX file that provides special file semantics.*
- class [File](#)  
*The basic interface for an open POSIX file.*
- class [Mman](#)  
*Interface for POSIX memory management.*
- class [File\\_system](#)  
*Basic interface for an L4Re::Vfs file system.*
- class [Fs](#)  
*POSIX File-system related functionality.*
- class [Ops](#)  
*Interface for the POSIX backends of an application.*

#### Functions

- [L4Re::Vfs::Ops](#) \*vfs\_ops **asm** ("l4re\_env\_posix\_vfs\_ops")  
*Reference to the applications L4Re::Vfs::Ops singleton.*

### 14.13.1 Detailed Description

Virtual file system for interfaces in POSIX libc.

## 14.14 L4vbus Namespace Reference

C++ interface of the [Vbus](#) API.

### Data Structures

- class [Pm](#)  
*Power-management API mixin.*
- class [Device](#)  
*Device on a [L4vbus::Vbus](#).*
- class [Icu](#)  
*Vbus Interrupt controller API.*
- class [Vbus](#)  
*The virtual bus ([Vbus](#)) interface.*
- class [Gpio\\_pin](#)  
*A GPIO pin.*
- class [Gpio\\_module](#)  
*A [Gpio\\_module](#) groups multiple GPIO pins together.*
- class [Pci\\_host\\_bridge](#)  
*A Pci host bridge.*
- class [Pci\\_dev](#)  
*A PCI device.*

### 14.14.1 Detailed Description

C++ interface of the [Vbus](#) API.

The virtual bus ([Vbus](#)) is a hierarchical (tree) structure of device nodes where each device has a set of resources attached to it. Each virtual bus provides an [Icu](#) ([Interrupt controller](#)) for interrupt handling.

The [Vbus](#) interface allows a client to find and query devices present on his virtual bus. After obtaining a device handle for a specific device the client can enumerate its resources.

Refer to [L4 Vbus functions](#) for the C API.

#### Include File

```
#include <l4/vbus/vbus>
```

#### Include File

```
#include <l4/vbus/vbus_gpio>
```

#### Include File

```
#include <l4/vbus/vbus_pci>
```

## 14.15 L4virtio Namespace Reference

L4-VIRTIO Transport C++ API.

### Data Structures

- class [Device](#)  
*IPC interface for virtio over [L4](#) IPC.*
- class [Ptr](#)  
*Pointer used in virtio descriptors.*
- class [Virtqueue](#)  
*Low-level [Virtqueue](#).*

### 14.15.1 Detailed Description

L4-VIRTIO Transport C++ API.

## Chapter 15


# Data Structure Documentation

### 15.1 Buffer Struct Reference


Data buffer used to transfer packets.

```
#include <virtio_net_buffer.h>
```

Inheritance diagram for Buffer:



Collaboration diagram for Buffer:



### Additional Inherited Members

### Public Member Functions inherited from [L4virtio::Svr::Data\\_buffer](#)

- `template<typename T>`  
`Data_buffer (T *p)`  
*Create buffer for object `p`.*
- `template<typename T>`  
`void set (T *p)`  
*Set buffer for object `p`.*
- `l4_uint32_t copy_to (Data_buffer *dst, l4_uint32_t max=UINT_MAX)`  
*Copy contents from this buffer to the destination buffer.*
- `l4_uint32_t skip (l4_uint32_t bytes)`  
*Skip given number of bytes in this buffer.*
- `bool done () const`  
*Check if there are no more bytes left in the buffer.*

### Data Fields inherited from [L4virtio::Svr::Data\\_buffer](#)

- `char * pos`  
*Current buffer position.*
- `l4_uint32_t left`  
*Bytes left in buffer.*



### 15.1.1 Detailed Description

Data buffer used to transfer packets.

Definition at line 19 of file [virtio\\_net\\_buffer.h](#).

The documentation for this struct was generated from the following file:

- `pkg/virtio-net-switch/server/switch/virtio_net_buffer.h`

## 15.2 `cxx::arith::Ld< V >` Struct Template Reference

Computes the binary logarithm of the given number at compile time.

```
#include <arith>
```

Collaboration diagram for `cxx::arith::Ld< V >`:



### 15.2.1 Detailed Description

```
template<unsigned long V>
struct cxx::arith::Ld< V >
```

Computes the binary logarithm of the given number at compile time.

#### Parameters

<i>val</i>	Number whose logarithm to compute, must be greater than zero.
------------	---

#### Returns

The binary logarithm of `val`.

Definition at line 48 of file [arith](#).

The documentation for this struct was generated from the following file:


- `l4/cxx/arith`

## 15.3 cxx::Avl\_map< KEY\_TYPE, DATA\_TYPE, COMPARE, ALLOC > Class Template Reference


AVL tree based associative container.

```
#include <avl_map>
```

Inheritance diagram for cxx::Avl\_map< KEY\_TYPE, DATA\_TYPE, COMPARE, ALLOC >:



Collaboration diagram for `cxx::Avl_map< KEY_TYPE, DATA_TYPE, COMPARE, ALLOC >`:



## Public Types

- `typedef COMPARE< KEY_TYPE > Key_compare`  
*Type of the comparison functor.*
- `typedef KEY_TYPE Key_type`  
*Type of the key values.*
- `typedef DATA_TYPE Data_type`

*Type of the data values.*

- typedef Base\_type::Node **Node**

*Return type for find.*

- typedef Base\_type::Node\_allocator **Node\_allocator**

*Type of the allocator.*

## Public Types inherited from

**cxx::Bits::Base\_avl\_set**< Pair< KEY\_TYPE, DATA\_TYPE >, Lt\_functor< KEY\_TYPE >, New\_allocator,

- enum  
*Return status constants.*
- typedef Pair< KEY\_TYPE, DATA\_TYPE > **Item\_type**  
*Type for the items store in the set.*
- typedef Bits::Avl\_map\_get\_key< KEY\_TYPE > **Get\_key**  
*Key-getter type to derive the sort key of an internal node.*
- typedef Bits::Avl\_map\_get\_key< KEY\_TYPE >::Key\_type **Key\_type**  
*Type of the sort key used for the items.*
- typedef Type\_traits< Item\_type >::Const\_type **Const\_item\_type**  
*Type used for const items within the set.*
- typedef Lt\_functor< KEY\_TYPE > **Item\_compare**  
*Type for the comparison functor.*
- typedef New\_allocator< \_Node > **Node\_allocator**  
*Type for the node allocator.*
- typedef Avl\_set\_iter< \_Node, Item\_type, Fwd > **Iterator**  
*Forward iterator for the set.*
- typedef Avl\_set\_iter< \_Node, Const\_item\_type, Fwd > **Const\_iterator**  
*Constant forward iterator for the set.*
- typedef Avl\_set\_iter< \_Node, Item\_type, Rev > **Rev\_iterator**  
*Backward iterator for the set.*
- typedef Avl\_set\_iter< \_Node, Const\_item\_type, Rev > **Const\_rev\_iterator**  
*Constant backward iterator for the set.*

## Public Member Functions

- Avl\_map (Node\_allocator const &alloc=Node\_allocator())  
*Create an empty AVL-tree based map.*
- cxx::Pair< Iterator, int > insert (Key\_type const &key, Data\_type const &data)  
*Insert a <key, data> pair into the map.*
- template<typename... Args>  
cxx::Pair< Iterator, int > emplace (Args &&...args)  
*Eplace a pair into the map.*
- Data\_type const & operator[] (Key\_type const &key) const  
*Get the data for the given key.*
- Data\_type & operator[] (Key\_type const &key)  
*Get or insert data for the given key.*

**Public Member Functions inherited from****`cxx::Bits::Base_avl_set< Pair< KEY_TYPE, DATA_TYPE >, Lt_func< KEY_TYPE >, New_allocator,`**

- `Base_avl_set (Node_allocator const &alloc=Node_allocator())`  
*Create a AVL-tree based set.*
- `Base_avl_set & operator= (Base_avl_set const &o)`  
*Copy assignment operator of an AVL-tree based set.*
- `cxx::Pair< Iterator, int > insert (Item_type const &item)`  
*Insert an item into the set.*
- `void clear () noexcept`  
*Remove all items from the set.*
- `int remove (Key_type const &item)`  
*Remove an item from the set.*
- `int erase (Key_type const &item)`  
*Erase the item with the given key.*
- `Node find_node (Key_type const &item) const`  
*Lookup a node equal to `item`.*
- `Node lower_bound_node (Key_type const &key) const`  
*Find the first node greater or equal to `key`.*
- `Const_iterator begin () const`  
*Get the constant forward iterator for the first element in the set.*
- `Const_iterator end () const`  
*Get the end marker for the constant forward iterator.*
- `Const_rev_iterator rbegin () const`  
*Get the constant backward iterator for the last element in the set.*
- `Const_rev_iterator rend () const`  
*Get the end marker for the constant backward iterator.*

**15.3.1 Detailed Description**

```
template<typename KEY_TYPE, typename DATA_TYPE, template< typename A > class COMPARE = Lt_↵
func<, template< typename B > class ALLOC = New_allocator>
class cxx::Avl_map< KEY_TYPE, DATA_TYPE, COMPARE, ALLOC >
```

AVL tree based associative container.

**Template Parameters**

<code>KEY_TYPE</code>	Type of the key values.
<code>DATA_TYPE</code>	Type of the data values.
<code>COMPARE</code>	Type comparison functor for the key values.
<code>ALLOC</code>	Type of the allocator used for the nodes.

Definition at line 45 of file [avl\\_map](#).

## 15.3.2 Constructor & Destructor Documentation

### 15.3.2.1 Avl\_map()

```
template<typename KEY_TYPE, typename DATA_TYPE, template< typename A > class COMPARE = Lt_↔
functor, template< typename B > class ALLOC = New_allocator>
cxx::Avl_map< KEY_TYPE, DATA_TYPE, COMPARE, ALLOC >::Avl_map (
    Node_allocator const & alloc = Node_allocator()) [inline]
```

Create an empty AVL-tree based map.

#### Parameters

<i>alloc</i>	The node allocator.
--------------	---------------------

Definition at line 80 of file [avl\\_map](#).

## 15.3.3 Member Function Documentation

### 15.3.3.1 emplace()

```
template<typename KEY_TYPE, typename DATA_TYPE, template< typename A > class COMPARE = Lt_↔
functor, template< typename B > class ALLOC = New_allocator>
template<typename... Args>
cxx::Pair< Iterator, int > cxx::Avl_map< KEY_TYPE, DATA_TYPE, COMPARE, ALLOC >::emplace (
    Args &&... args) [inline]
```

Emplace a pair into the map.

#### Parameters

<i>args</i>	The <a href="#">cxx::Pair</a> constructor arguments for key & value.
-------------	--

#### Returns

A pair of iterator (*first*) and return value (*second*). *second* will be 0 if the element was inserted into the set and `−#E_exist` if the key was already in the set and the set was therefore not updated. In both cases, *first* contains an iterator that points to the element. *second* may also be `−#E_nomem` when memory for the new node could not be allocated. *first* is then invalid.

Definition at line 117 of file [avl\\_map](#).

### 15.3.3.2 insert()

```
template<typename KEY_TYPE, typename DATA_TYPE, template< typename A > class COMPARE = Lt_↵
functor, template< typename B > class ALLOC = New_allocator>
cxx::Pair< Iterator, int > cxx::Avl_map< KEY_TYPE, DATA_TYPE, COMPARE, ALLOC >::insert (
    Key_type const & key,
    Data_type const & data) [inline]
```

Insert a <key, data> pair into the map.

#### Parameters

<i>key</i>	The key value.
<i>data</i>	The data value to insert.


#### Returns

A pair of iterator (*first*) and return value (*second*). *second* will be 0 if the element was inserted into the set and `-#E_exist` if the key was already in the set and the set was therefore not updated. In both cases, *first* contains an iterator that points to the element. *second* may also be `-#E_nomem` when memory for the new node could not be allocated. *first* is then invalid.

Definition at line 99 of file [avl\\_map](#).

Referenced by [cxx::Avl\\_map< Region, Hdlr, cxx::Lt\\_functor, Alloc >::operator\[\]\(\)](#).

Here is the caller graph for this function:



### 15.3.3.3 operator[]() [1/2]

```
template<typename KEY_TYPE, typename DATA_TYPE, template< typename A > class COMPARE = Lt_↵
functor, template< typename B > class ALLOC = New_allocator>
Data_type & cxx::Avl_map< KEY_TYPE, DATA_TYPE, COMPARE, ALLOC >::operator[] (
    Key_type const & key) [inline]
```

Get or insert data for the given key.

#### Parameters

<i>key</i>	The key value to use for lookup.
------------	----------------------------------

#### Returns

If the item already exists, a reference to the data item. Otherwise a new data item is default-constructed and inserted under the given key before a reference is returned.

Definition at line 137 of file [avl\\_map](#).

#### 15.3.3.4 operator[]() [2/2]

```
template<typename KEY_TYPE, typename DATA_TYPE, template< typename A > class COMPARE = Lt_↔
functor, template< typename B > class ALLOC = New_allocator>
Data_type const & cxx::Avl_map< KEY_TYPE, DATA_TYPE, COMPARE, ALLOC >::operator[] (
    Key_type const & key) const [inline]
```

Get the data for the given key.

#### Parameters

<i>key</i>	The key value to use for lookup.
------------	----------------------------------

#### Precondition

A <key, data> pair for the given key value must exist.

Definition at line 125 of file [avl\\_map](#).

The documentation for this class was generated from the following file:

- I4/cxx/[avl\\_map](#)


## 15.4 cxx::Avl\_set< ITEM\_TYPE, COMPARE, ALLOC > Class Template Reference

AVL set for simple comparable items.


```
#include <avl_set>
```



Inheritance diagram for cxx::Avl\_set< ITEM\_TYPE, COMPARE, ALLOC >:



Collaboration diagram for `cxx::Avl_set< ITEM_TYPE, COMPARE, ALLOC >`:



### Additional Inherited Members

### Public Types inherited from

`cxx::Bits::Base_avl_set< ITEM_TYPE, Lt_funcionr < ITEM_TYPE >, New_allocator, Bits::Avl_set_get_key`

- `enum`

*Return status constants.*

- typedef `ITEM_TYPE` **Item\_type**  
*Type for the items store in the set.*
- typedef `Bits::Avl_set_get_key< ITEM_TYPE >` **Get\_key**  
*Key-getter type to derive the sort key of an internal node.*
- typedef `Bits::Avl_set_get_key< ITEM_TYPE >::Key_type` **Key\_type**  
*Type of the sort key used for the items.*
- typedef `Type_traits< Item_type >::Const_type` **Const\_item\_type**  
*Type used for const items within the set.*
- typedef `Lt_funcitor< ITEM_TYPE >` **Item\_compare**  
*Type for the comparison functor.*
- typedef `New_allocator< _Node >` **Node\_allocator**  
*Type for the node allocator.*
- typedef `Avl_set_iter< _Node, Item_type, Fwd >` **Iterator**  
*Forward iterator for the set.*
- typedef `Avl_set_iter< _Node, Const_item_type, Fwd >` **Const\_iterator**  
*Constant forward iterator for the set.*
- typedef `Avl_set_iter< _Node, Item_type, Rev >` **Rev\_iterator**  
*Backward iterator for the set.*
- typedef `Avl_set_iter< _Node, Const_item_type, Rev >` **Const\_rev\_iterator**  
*Constant backward iterator for the set.*

### Public Member Functions inherited from

`cxx::Bits::Base_avl_set< ITEM_TYPE, Lt_funcitor< ITEM_TYPE >, New_allocator, Bits::Avl_set_get_key`

- `Base_avl_set` (`Node_allocator` const &alloc=`Node_allocator`())  
*Create a AVL-tree based set.*
- `Base_avl_set` & `operator=` (`Base_avl_set` const &o)  
*Copy assignment operator of an AVL-tree based set.*
- `cxx::Pair< Iterator, int >` `insert` (`Item_type` const &item)  
*Insert an item into the set.*
- void **clear** () noexcept  
*Remove all items from the set.*
- int `remove` (`Key_type` const &item)  
*Remove an item from the set.*
- int `erase` (`Key_type` const &item)  
*Erase the item with the given key.*
- Node `find_node` (`Key_type` const &item) const  
*Lookup a node equal to `item`.*
- Node `lower_bound_node` (`Key_type` const &key) const  
*Find the first node greater or equal to `key`.*
- `Const_iterator` `begin` () const  
*Get the constant forward iterator for the first element in the set.*
- `Const_iterator` `end` () const  
*Get the end marker for the constant forward iterator.*
- `Const_rev_iterator` `rbegin` () const  
*Get the constant backward iterator for the last element in the set.*
- `Const_rev_iterator` `rend` () const  
*Get the end marker for the constant backward iterator.*

### 15.4.1 Detailed Description

```
template<typename ITEM_TYPE, template< typename T > class COMPARE = Lt_functor, template< type-  
name A > class ALLOC = New_allocator>  
class cxx::Avl_set< ITEM_TYPE, COMPARE, ALLOC >
```

AVL set for simple comparable items.

The AVL set can store any kind of items where a partial order is defined. The default relation is defined by the '<' operator.

#### Template Parameters

<i>ITEM_TYPE</i>	The type of the items to be stored in the set.
<i>COMPARE</i>	The relation to define the partial order, default is to use operator '<'. 
<i>ALLOC</i>	The allocator to use for the nodes of the AVL set.

Definition at line 538 of file [avl\\_set](#).

The documentation for this class was generated from the following file:

- [l4/cxx/avl\\_set](#)

## 15.5 cxx::Avl\_tree< Node, Get\_key, Compare > Class Template Reference


A generic AVL tree.

```
#include <avl_tree>
```

Inheritance diagram for cxx::Avl\_tree< Node, Get\_key, Compare >:



Collaboration diagram for `cxx::Avl_tree< Node, Get_key, Compare >`:



## Public Types

- typedef `Bst::Iterator` `Iterator`

- typedef [Bst::Const\\_iterator](#) **Const\_iterator**  
*Constant forward iterator for the tree.*
- typedef [Bst::Rev\\_iterator](#) **Rev\_iterator**  
*Backward iterator for the tree.*
- typedef [Bst::Const\\_rev\\_iterator](#) **Const\_rev\_iterator**  
*Constant backward iterator for the tree.*

## Public Types inherited from [cxx::Bits::Bst< Node, Get\\_key, Compare >](#)

- typedef [Get\\_key::Key\\_type](#) **Key\_type**  
*The type of key values used to generate the total order of the elements.*
- typedef [Type\\_traits< \[Key\\\_type\]\(#\) >::Param\\_type](#) **Key\_param\_type**  
*The type for key parameters.*
- typedef [Fwd](#) **Fwd\_iter\_ops**  
*Helper for building forward iterators for different wrapper classes.*
- typedef [Rev](#) **Rev\_iter\_ops**  
*Helper for building reverse iterators for different wrapper classes.*
- typedef [\\_\\_Bst\\_iter< Node, Node, Fwd >](#) **Iterator**  
*Forward iterator.*
- typedef [\\_\\_Bst\\_iter< Node, Node const, Fwd >](#) **Const\_iterator**  
*Constant forward iterator.*
- typedef [\\_\\_Bst\\_iter< Node, Node, Rev >](#) **Rev\_iterator**  
*Backward iterator.*
- typedef [\\_\\_Bst\\_iter< Node, Node const, Rev >](#) **Const\_rev\_iterator**  
*Constant backward.*

## Public Member Functions

- [Pair< Node \\*, bool >](#) [insert](#) (Node \*new\_node)  
*Insert a new node into this AVL tree.*
- Node \* [remove](#) (Key\_param\_type key)  
*Remove the node with key from the tree.*
- Node \* [erase](#) (Key\_param\_type key)  
*An alias for [remove\(\)](#).*
- [Avl\\_tree](#) ()=default  
*Create an empty AVL tree.*
- [~Avl\\_tree](#) () noexcept  
*Destroy the tree.*

## Public Member Functions inherited from `cxx::Bits::Bst< Node, Get_key, Compare >`

- `Const_iterator begin ()` const  
*Get the constant forward iterator for the first element in the set.*
- `Const_iterator end ()` const  
*Get the end marker for the constant forward iterator.*
- `Iterator begin ()`  
*Get the mutable forward iterator for the first element of the set.*
- `Iterator end ()`  
*Get the end marker for the mutable forward iterator.*
- `Const_rev_iterator rbegin ()` const  
*Get the constant backward iterator for the last element in the set.*
- `Const_rev_iterator rend ()` const  
*Get the end marker for the constant backward iterator.*
- `Rev_iterator rbegin ()`  
*Get the mutable backward iterator for the last element of the set.*
- `Rev_iterator rend ()`  
*Get the end marker for the mutable backward iterator.*
  
- `Node * find_node (Key_param_type key)` const  
*find the node with the given key.*
- `Node * lower_bound_node (Key_param_type key)` const  
*Find the first node with a key not less than the given `key`.*
- `Const_iterator find (Key_param_type key)` const  
*find the node with the given key.*
- `template<typename FUNC>`  
`void remove_all (FUNC &&callback)`  
*Clear the tree.*

## Additional Inherited Members

- `Bst ()`  
*Create an empty tree.*
  
- `Node * head ()` const  
*Access the head node as object of type `Node`.*

## Static Protected Member Functions inherited from `cxx::Bits::Bst< Node, Get_key, Compare >`

- `template<typename FUNC>`  
`static void remove_tree (Bst_node *head, FUNC &&callback)`  
*Remove all elements in the subtree of head.*
  
- `static Key_type k (Bst_node const *n)`  
*Get the key value of `n`.*
  
- `static Dir dir (Key_param_type l, Key_param_type r)`



*Get the direction to go from  $l$  to search for  $r$ .*

- static Dir **dir** (Key\_param\_type  $l$ , Bst\_node const  $*r$ )

*Get the direction to go from  $l$  to search for  $r$ .*

- static bool **greater** (Key\_param\_type  $l$ , Key\_param\_type  $r$ )

*Is  $l$  greater than  $r$ .*

- static bool **greater** (Key\_param\_type  $l$ , Bst\_node const  $*r$ )

*Is  $l$  greater than  $r$ .*

- static bool **greater** (Bst\_node const  $*l$ , Bst\_node const  $*r$ )

*Is  $l$  greater than  $r$ .*

- Bst\_node  $*\_head$

*The head pointer of the tree.*

### 15.5.1 Detailed Description

```
template<typename Node, typename Get_key, typename Compare = Lt_functor<typename Get_key::Key↵
_type>>
class cxx::Avl_tree< Node, Get_key, Compare >
```

A generic AVL tree.

#### Template Parameters

<i>Node</i>	The data type of the nodes (must inherit from <a href="#">Avl_tree_node</a> ).
<i>Get_key</i>	The meta function to get the key value from a node. The implementation uses <code>Get_key::key↵_of(ptr_to_node)</code> . The type of the key values must be defined in <code>Get_key::Key_type</code> .
<i>Compare</i>	Binary relation to establish a total order for the nodes of the tree. <code>Compare() (l, r)</code> must return true if the key $l$ is smaller than the key $r$ .

This implementation does not provide any memory management. It is the responsibility of the caller to allocate nodes before inserting them and to free them when they are removed or when the tree is destroyed. Conversely, the caller must also ensure that nodes are removed from the tree before they are destroyed.

#### Examples

[tmpfs/lib/src/fs.cc](#).

Definition at line 100 of file [avl\\_tree](#).

## 15.5.2 Member Typedef Documentation

### 15.5.2.1 Iterator

```
template<typename Node, typename Get_key, typename Compare = Lt_functor<typename Get_key::←
Key_type>>>
typedef Bst::Iterator cxx::Avl_tree< Node, Get_key, Compare >::Iterator
```

Forward iterator for the tree.

Definition at line 130 of file [avl\\_tree](#).

## 15.5.3 Member Function Documentation

### 15.5.3.1 insert()

```
template<typename Node, typename Get_key, class Compare>
Pair< Node *, bool > cxx::Avl_tree< Node, Get_key, Compare >::insert (
    Node * new_node)
```

Insert a new node into this AVL tree.

#### Parameters

<i>new_node</i>	A pointer to the new node.
-----------------	----------------------------


#### Returns

A pair, with *second* set to `true` and *first* pointing to *new\_node*, on success. If there is already a node with the same key then *first* points to this node and *second* is 'false'.

Definition at line 220 of file [avl\\_tree](#).

References [cxx::Bits::Bst< Node, Get\\_key, Compare >::dir\(\)](#), [cxx::Bits::Bst< Node, Get\\_key, Compare >::greater\(\)](#), and [cxx::Bits::Direction::N](#).

Here is the call graph for this function:



### 15.5.3.2 remove()

```
template<typename Node, typename Get_key, class Compare>
Node * cxx::Avl_tree< Node, Get_key, Compare >::remove (
    Key_param_type key) [inline]
```

Remove the node with *key* from the tree.

#### Parameters

<i>key</i>	The key to the node to remove.
------------	--------------------------------

#### Returns


The pointer to the removed node on success, or 0 if no node with the *key* exists.

Definition at line 282 of file [avl\\_tree](#).

References [cxx::Bits::Bst< Node, Get\\_key, Compare >::dir\(\)](#), [cxx::Bits::Bst< Node, Get\\_key, Compare >::greater\(\)](#), [cxx::Bits::Direction::L](#), and [cxx::Bits::Direction::N](#).

Referenced by [cxx::Avl\\_tree< Entry, Names\\_get\\_key >::erase\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



The documentation for this class was generated from the following file:


- [I4/cxx/avl\\_tree](#)

## 15.6 cxx::Avl\_tree\_node Class Reference


Node of an AVL tree.

```
#include <avl_tree>
```

Inheritance diagram for cxx::Avl\_tree\_node:



Collaboration diagram for cxx::Avl\_tree\_node:



### Protected Member Functions

- **Avl\_tree\_node ()**=default  
*Create an uninitialized node, this is what you should do.*

### Protected Member Functions inherited from [cxx::Bits::Bst\\_node](#)

- **Bst\_node ()**  
*Create uninitialized node.*
- **Bst\_node (bool)**  
*Create initialized node.*

## Additional Inherited Members

### Static Protected Member Functions inherited from [cxx::Bits::Bst\\_node](#)

- static [Bst\\_node](#) \* **next** ([Bst\\_node](#) const \*p, [Direction](#) d)  
*Get next node in direction d.*
- static void **next** ([Bst\\_node](#) \*p, [Direction](#) d, [Bst\\_node](#) \*n)  
*Set next node of p in direction d to n.*
- static [Bst\\_node](#) \*\* **next\_p** ([Bst\\_node](#) \*p, [Direction](#) d)  
*Get pointer to link in direction d.*
- template<typename Node>  
static Node \* **next** ([Bst\\_node](#) const \*p, [Direction](#) d)  
*Get next node in direction d as type Node.*
- static void **rotate** ([Bst\\_node](#) \*\*t, [Direction](#) idir)  
*Rotate subtree t in the opposite direction of idir.*

## 15.6.1 Detailed Description

Node of an AVL tree.

### Examples

[tmpfs/lib/src/fs.cc](#).

Definition at line 29 of file [avl\\_tree](#).

The documentation for this class was generated from the following file:


- [l4/cxx/avl\\_tree](#)

## 15.7 [cxx::Base\\_slab](#)< [Obj\\_size](#), [Slab\\_size](#), [Max\\_free](#), [Alloc](#) > Class Template Reference


Basic slab allocator.

```
#include <slab_alloc>
```

Inheritance diagram for cxx::Base\_slab< Obj\_size, Slab\_size, Max\_free, Alloc >:



Collaboration diagram for cxx::Base\_slab< Obj\_size, Slab\_size, Max\_free, Alloc >:



## Data Structures

- struct [Slab\\_i](#)

*Type of a slab.*

## Public Types

- enum { [object\\_size](#) = Obj\_size , [slab\\_size](#) = Slab\_size , [objects\\_per\\_slab](#) = (Slab\_size - sizeof(Slab\_head)) / object\_size , [max\\_free\\_slabs](#) = Max\_free }
- typedef Alloc< [Slab\\_i](#) > **Slab\_alloc**  
*Type of the backend allocator.*

## Public Member Functions

- void \* [alloc](#) () noexcept  
*Allocate a new object.*
- void [free](#) (void \* \_o) noexcept  
*Free the given object (\_o).*
- unsigned [total\\_objects](#) () const noexcept  
*Get the total number of objects managed by the slab allocator.*
- unsigned [free\\_objects](#) () const noexcept  
*Get the number of objects which can be allocated before a new empty slab needs to be added to the slab allocator.*

### 15.7.1 Detailed Description

```
template<int Obj_size, int Slab_size = L4_PAGESIZE, int Max_free = 2, template< typename A > class Alloc
= New_allocator>
class cxx::Base_slab< Obj_size, Slab_size, Max_free, Alloc >
```

Basic slab allocator.

#### Template Parameters

<i>Obj_size</i>	The size of the objects managed by the allocator (in bytes).
<i>Slab_size</i>	The size of a slab (in bytes).
<i>Max_free</i>	The maximum number of free slabs. When this limit is reached slabs are freed, provided that the backend allocator supports allocated memory to be freed.
<i>Alloc</i>	The backend allocator used to allocate slabs.

Definition at line 31 of file [slab\\_alloc](#).



## 15.7.2 Member Enumeration Documentation

### 15.7.2.1 anonymous enum

```
template<int Obj_size, int Slab_size = L4_PAGESIZE, int Max_free = 2, template< typename A >
class Alloc = New_allocator>
anonymous enum
```

#### Enumerator

<code>object_size</code>	Size of an object.
<code>slab_size</code>	Size of a slab.
<code>objects_per_slab</code>	Objects per slab.
<code>max_free_slabs</code>	Maximum number of free slabs.

Definition at line 65 of file [slab\\_alloc](#).

## 15.7.3 Member Function Documentation

### 15.7.3.1 `alloc()`

```
template<int Obj_size, int Slab_size = L4_PAGESIZE, int Max_free = 2, template< typename A >
class Alloc = New_allocator>
void * cxx::Base\_slab< Obj_size, Slab_size, Max_free, Alloc >::alloc () [inline], [noexcept]
```

Allocate a new object.

#### Returns

A pointer to the new object if the allocation succeeds, or 0 on failure to acquire memory from the backend allocator when the slab cache memory is already exhausted.

#### Note

The user is responsible for initializing the object.

Definition at line 207 of file [slab\\_alloc](#).

### 15.7.3.2 `free()`

```
template<int Obj_size, int Slab_size = L4_PAGESIZE, int Max_free = 2, template< typename A >
class Alloc = New_allocator>
void cxx::Base\_slab< Obj_size, Slab_size, Max_free, Alloc >::free (
    void * _o) [inline], [noexcept]
```

Free the given object (`_o`).

#### Precondition

The object must have been allocated with this allocator.

Definition at line 246 of file [slab\\_alloc](#).

### 15.7.3.3 free\_objects()

```
template<int Obj_size, int Slab_size = L4_PAGESIZE, int Max_free = 2, template< typename A >
class Alloc = New_allocator>
unsigned cxx::Base_slab< Obj_size, Slab_size, Max_free, Alloc >::free_objects () const [inline],
[noexcept]
```

Get the number of objects which can be allocated before a new empty slab needs to be added to the slab allocator.

#### Returns

The number of free objects in the slab allocator.

Definition at line 308 of file [slab\\_alloc](#).

### 15.7.3.4 total\_objects()

```
template<int Obj_size, int Slab_size = L4_PAGESIZE, int Max_free = 2, template< typename A >
class Alloc = New_allocator>
unsigned cxx::Base_slab< Obj_size, Slab_size, Max_free, Alloc >::total_objects () const [inline],
[noexcept]
```

Get the total number of objects managed by the slab allocator.

#### Returns

The number of objects managed by the allocator (including the free objects).

Definition at line 299 of file [slab\\_alloc](#).

The documentation for this class was generated from the following file:


- l4/cxx/slab\_alloc

## 15.8 cxx::Base\_slab< Obj\_size, Slab\_size, Max\_free, Alloc >::Slab\_i Struct Reference

Type of a slab.

```
#include <slab_alloc>
```

Collaboration diagram for cxx::Base\_slab< Obj\_size, Slab\_size, Max\_free, Alloc >::Slab\_i:



### 15.8.1 Detailed Description

```
template<int Obj_size, int Slab_size = L4_PAGESIZE, int Max_free = 2, template< typename A > class Alloc
= New_allocator>
struct cxx::Base_slab< Obj_size, Slab_size, Max_free, Alloc >::Slab_i
```

Type of a slab.

Definition at line 86 of file [slab\\_alloc](#).

The documentation for this struct was generated from the following file:


- `l4/cxx/slab_alloc`

## 15.9 `cxx::Base_slab_static< Obj_size, Slab_size, Max_free, Alloc >` Class Template Reference


Merged slab allocator (allocators for objects of the same size are merged together).

```
#include <slab_alloc>
```

Inheritance diagram for `cxx::Base_slab_static< Obj_size, Slab_size, Max_free, Alloc >`:



Collaboration diagram for `cxx::Base_slab_static< Obj_size, Slab_size, Max_free, Alloc >`:



## Public Types

- enum { `object_size` = `Obj_size` , `slab_size` = `Slab_size` , `objects_per_slab` = `_A::objects_per_slab` , `max_free_slabs` = `Max_free` }

## Public Member Functions

- void \* `alloc` () noexcept  
*Allocate an object.*
- void `free` (void \*p) noexcept  
*Free the given object (p).*
- unsigned `total_objects` () const noexcept  
*Get the total number of objects managed by the slab allocator.*
- unsigned `free_objects` () const noexcept  
*Get the number of free objects in the slab allocator.*

### 15.9.1 Detailed Description

```

template<int Obj_size, int Slab_size = L4_PAGESIZE, int Max_free = 2, template< typename A > class Alloc
= New_allocator>
class cxx::Base_slab_static< Obj_size, Slab_size, Max_free, Alloc >
  
```

Merged slab allocator (allocators for objects of the same size are merged together).

## Template Parameters

<i>Obj_size</i>	The size of an object managed by the slab allocator.
<i>Slab_size</i>	The size of a slab.

<i>Max_free</i>	The maximum number of free slabs.
<i>Alloc</i>	The allocator for the slabs.

This slab allocator class is useful for merging slab allocators with the same parameters (equal `Obj_size`, `Slab_size`, `Max_free`, and `Alloc` parameters) together and share the overhead for the slab caches among all equal-sized objects.

Definition at line 388 of file [slab\\_alloc](#).

## 15.9.2 Member Enumeration Documentation

### 15.9.2.1 anonymous enum

```
template<int Obj_size, int Slab_size = L4_PAGESIZE, int Max_free = 2, template< typename A >
class Alloc = New_allocator>
anonymous enum
```

#### Enumerator

<code>object_size</code>	Size of an object.
<code>slab_size</code>	Size of a slab.
<code>objects_per_slab</code>	Number of objects per slab.
<code>max_free_slabs</code>	Maximum number of free slabs.

Definition at line 395 of file [slab\\_alloc](#).

## 15.9.3 Member Function Documentation

### 15.9.3.1 `alloc()`

```
template<int Obj_size, int Slab_size = L4_PAGESIZE, int Max_free = 2, template< typename A >
class Alloc = New_allocator>
void * cxx::Base\_slab\_static< Obj_size, Slab_size, Max_free, Alloc >::alloc () [inline],
[noexcept]
```

Allocate an object.

#### Note

The user is responsible for initializing the object.

Definition at line 412 of file [slab\\_alloc](#).

### 15.9.3.2 free()

```
template<int Obj_size, int Slab_size = L4_PAGESIZE, int Max_free = 2, template< typename A >
class Alloc = New_allocator>
void cxx::Base_slab_static< Obj_size, Slab_size, Max_free, Alloc >::free (
    void * p) [inline], [noexcept]
```

Free the given object (p).

#### Parameters

<i>p</i>	The pointer to the object to free.
----------	------------------------------------

#### Precondition

*p* must be a pointer to an object allocated by this allocator.

Definition at line 420 of file [slab\\_alloc](#).

### 15.9.3.3 free\_objects()

```
template<int Obj_size, int Slab_size = L4_PAGESIZE, int Max_free = 2, template< typename A >
class Alloc = New_allocator>
unsigned cxx::Base_slab_static< Obj_size, Slab_size, Max_free, Alloc >::free_objects () const
[inline], [noexcept]
```

Get the number of free objects in the slab allocator.

#### Returns

The number of free objects in all free and partially used slabs managed by this allocator.

#### Note

The value is the merged value for all equal parameterized [Base\\_slab\\_static](#) instances.

Definition at line 440 of file [slab\\_alloc](#).

### 15.9.3.4 total\_objects()

```
template<int Obj_size, int Slab_size = L4_PAGESIZE, int Max_free = 2, template< typename A >
class Alloc = New_allocator>
unsigned cxx::Base_slab_static< Obj_size, Slab_size, Max_free, Alloc >::total_objects () const
[inline], [noexcept]
```

Get the total number of objects managed by the slab allocator.

#### Returns

The number of objects managed by the allocator (including the free objects).

#### Note

The value is the merged value for all equal parameterized [Base\\_slab\\_static](#) instances.

Definition at line 430 of file [slab\\_alloc](#).

The documentation for this class was generated from the following file:

- `I4/cxx/slab_alloc`

## 15.10 `cxx::Bitfield< T, LSB, MSB >` Class Template Reference


Definition for a member (part) of a bit field.

```
#include <bitfield>
```

Inheritance diagram for `cxx::Bitfield< T, LSB, MSB >`:



Collaboration diagram for `cxx::Bitfield< T, LSB, MSB >`:



### Data Structures

- class [Value\\_base](#)  
*Internal helper type.*
- class [Value](#)  
*Internal helper type.*
- class [Value\\_unshifted](#)  
*Internal helper type.*



## Public Types

- enum { **Bits** = MSB + 1 - LSB , **Lsb** = LSB , **Msb** = MSB }
- typedef Best\_type< **Bits** >::Type **Bits\_type**  
*Type to hold at least **Bits** bits.*
- typedef Best\_type< **Bits**+**Lsb** >::Type **Shift\_type**  
*Type to hold at least **Bits** + **Lsb** bits.*
- typedef **Value**< Base\_type & > **Ref**  
*Reference type to access the bits inside a raw bit field.*
- typedef **Value**< Base\_type volatile & > **Ref\_volatile**  
*Volatile reference type to access the bits inside a raw bit field.*
- typedef **Value**< Base\_type const > **Val**  
***Value** type to access the bits inside a raw bit field.*
- typedef **Value\_unshifted**< Base\_type & > **Ref\_unshifted**  
*Reference type to access the bits inside a raw bit field (in place).*
- typedef **Value\_unshifted**< Base\_type volatile & > **Ref\_unshifted\_volatile**  
*Volatile reference type to access the bits inside a raw bit field (in place).*
- typedef **Value\_unshifted**< Base\_type const > **Val\_unshifted**  
***Value** type to access the bits inside a raw bit field (in place).*

## Static Public Member Functions

- static constexpr **Bits\_type** **get** (**Shift\_type** val)  
*Get the bits out of **val**.*
- static constexpr Base\_type **get\_unshifted** (**Shift\_type** val)  
*Get the bits in place out of **val**.*
- static constexpr Base\_type **set\_dirty** (Base\_type dest, **Shift\_type** val)  
*Set the bits corresponding to **val**.*
- static constexpr Base\_type **set\_unshifted\_dirty** (Base\_type dest, **Shift\_type** val)  
*Set the bits corresponding to **val**.*
- static Base\_type **set** (Base\_type dest, **Bits\_type** val)  
*Set the bits corresponding to **val**.*
- static Base\_type **set\_unshifted** (Base\_type dest, **Shift\_type** val)  
*Set the bits corresponding to **val**.*
- static constexpr Base\_type **val\_dirty** (**Shift\_type** val)  
*Get the shifted bits for **val**.*
- static constexpr Base\_type **val** (**Bits\_type** val)  
*Get the shifted bits for **val**.*
- static constexpr Base\_type **val\_unshifted** (**Shift\_type** val)  
*Get the shifted bits for **val**.*

## Static Public Attributes

- static constexpr Base\_type **Low\_mask** = Base\_type(~0ULL) >> (sizeof(Base\_type) \* 8 - **Bits**)  
*Mask value to get **Bits** bits.*
- static constexpr Base\_type **Mask** = **Low\_mask** << **Lsb**  
*Mask value to the bits out of a **T**.*

### 15.10.1 Detailed Description

```
template<typename T, unsigned LSB, unsigned MSB>  
class cxx::Bitfield< T, LSB, MSB >
```

Definition for a member (part) of a bit field.

#### Parameters

<i>T</i>	The underlying type of the bit field.
<i>LSB</i>	The least significant bit of our bits.
<i>MSB</i>	The most significant bit of our bits.

Definition at line 24 of file [bitfield](#).

### 15.10.2 Member Typedef Documentation

#### 15.10.2.1 Bits\_type

```
template<typename T, unsigned LSB, unsigned MSB>  
typedef Best_type<Bits>::Type cxx::Bitfield< T, LSB, MSB >::Bits_type
```

Type to hold at least [Bits](#) bits.

This type can handle all values that can be stored in this part of the bit field.

Definition at line 71 of file [bitfield](#).

#### 15.10.2.2 Shift\_type

```
template<typename T, unsigned LSB, unsigned MSB>  
typedef Best_type<Bits+Lsb>::Type cxx::Bitfield< T, LSB, MSB >::Shift_type
```

Type to hold at least [Bits](#) + [Lsb](#) bits.

This type can handle all values that can be stored in this part of the bit field when they are at the target location ([Lsb](#) bits shifted to the left).

Definition at line 79 of file [bitfield](#).

## 15.10.3 Member Enumeration Documentation

### 15.10.3.1 anonymous enum

```
template<typename T, unsigned LSB, unsigned MSB>
anonymous enum
```

#### Enumerator

Bits	Number of bits.
Lsb	index of the LSB
Msb	index of the MSB

Definition at line 52 of file [bitfield](#).

## 15.10.4 Member Function Documentation

### 15.10.4.1 `get()`

```
template<typename T, unsigned LSB, unsigned MSB>
constexpr Bits_type cxx::Bitfield< T, LSB, MSB >::get (
    Shift_type val) [inline], [static], [constexpr]
```

Get the bits out of `val`.

#### Parameters

<code>val</code>	The raw value of the whole bit field.
------------------	---------------------------------------

#### Returns

The bits from `Lsb` to `Msb` shifted to the right.

Definition at line 96 of file [bitfield](#).

### 15.10.4.2 `get_unshifted()`

```
template<typename T, unsigned LSB, unsigned MSB>
constexpr Base_type cxx::Bitfield< T, LSB, MSB >::get_unshifted (
    Shift_type val) [inline], [static], [constexpr]
```

Get the bits in place out of `val`.

#### Parameters

<code>val</code>	The raw value of the whole bit field.
------------------	---------------------------------------

#### Returns

The bits from `Lsb` to `Msb` (unshifted).

This means other bits are masked out, however the result is not shifted to the right.

Definition at line 109 of file [bitfield](#).

### 15.10.4.3 set()

```
template<typename T, unsigned LSB, unsigned MSB>
Base_type cxx::Bitfield< T, LSB, MSB >::set (
    Base_type dest,
    Bits_type val) [inline], [static]
```

Set the bits corresponding to `val`.

#### Parameters

<i>dest</i>	The current value of the whole bit field.
<i>val</i>	The value to set into the bits.

#### Returns

The new value of the whole bit field.

Definition at line 158 of file `bitfield`.

### 15.10.4.4 set\_dirty()

```
template<typename T, unsigned LSB, unsigned MSB>
constexpr Base_type cxx::Bitfield< T, LSB, MSB >::set_dirty (
    Base_type dest,
    Shift_type val) [inline], [static], [constexpr]
```

Set the bits corresponding to `val`.

#### Parameters

<i>dest</i>	The current value of the whole bit field.
<i>val</i>	The value to set into the bits.

#### Returns

The new value of the whole bit field.

#### Precondition

`val` must not contain more than `Bits` bits.

**Note**

This function does not mask `val` to the right number of bits.

Definition at line 124 of file `bitfield`.

Referenced by `cxx::Bitfield< decltype(raw), 0, 0 >::set()`.

Here is the caller graph for this function:

**15.10.4.5 set\_unshifted()**

```

template<typename T, unsigned LSB, unsigned MSB>
Base_type cxx::Bitfield< T, LSB, MSB >::set_unshifted (
    Base_type dest,
    Shift_type val) [inline], [static]
  
```

Set the bits corresponding to `val`.

**Parameters**

<i>dest</i>	The current value of the whole bit field.
<i>val</i>	The value shifted <code>Lsb</code> bits to the left that shall be set into the bit field.

**Returns**

the new value of the whole bit field.

Definition at line 170 of file `bitfield`.

**15.10.4.6 set\_unshifted\_dirty()**

```

template<typename T, unsigned LSB, unsigned MSB>
constexpr Base_type cxx::Bitfield< T, LSB, MSB >::set_unshifted_dirty (
    Base_type dest,
    Shift_type val) [inline], [static], [constexpr]
  
```

Set the bits corresponding to `val`.

**Parameters**

<i>dest</i>	The current value of the whole bit field.
<i>val</i>	The value shifted <a href="#">Lsb</a> bits to the left that shall be set into the bits.

**Returns**

The new value of the whole bit field.

**Precondition**

[val](#) must not contain more than [Bits](#) bits shifted [Lsb](#) bits to the left.


**Note**

This function does not mask [val](#) to the right number of bits.

Definition at line [144](#) of file [bitfield](#).

Referenced by [cxx::Bitfield< decltype\(raw\), 0, 0 >::set\\_unshifted\(\)](#).

Here is the caller graph for this function:

**15.10.4.7 val()**

```
template<typename T, unsigned LSB, unsigned MSB>
constexpr Base_type cxx::Bitfield< T, LSB, MSB >::val (
    Bits\_type val) [inline], [static], [constexpr]
```

Get the shifted bits for [val](#).

**Parameters**

<i>val</i>	The value to set into the bits.
------------	---------------------------------

**Returns**

The raw bit field value.

Definition at line [193](#) of file [bitfield](#).

15.10.4.8 `val_dirty()`

```
template<typename T, unsigned LSB, unsigned MSB>
constexpr Base_type cxx::Bitfield< T, LSB, MSB >::val_dirty (
    Shift_type val) [inline], [static], [constexpr]
```

Get the shifted bits for `val`.

## Parameters

<code>val</code>	The value to set into the bits.
------------------	---------------------------------

## Returns

The raw bit field value.

## Precondition

`val` must not contain more than `Bits` bits.


## Note

This function does not mask `val` to the right number of bits.

Definition at line 184 of file `bitfield`.

Referenced by `cxx::Bitfield< decltype(raw), 0, 0 >::val()`.

Here is the caller graph for this function:



#### 15.10.4.9 val\_unshifted()

```
template<typename T, unsigned LSB, unsigned MSB>
constexpr Base_type cxx::Bitfield< T, LSB, MSB >::val_unshifted (
    Shift_type val) [inline], [static], [constexpr]
```

Get the shifted bits for [val](#).

#### Parameters

<i>val</i>	The value shifted <a href="#">Lsb</a> bits to the left that shall be set into the bits.
------------	---

#### Returns

The raw bit field value.

Definition at line [203](#) of file [bitfield](#).

The documentation for this class was generated from the following file:


- [l4/cxx/bitfield](#)

## 15.11 cxx::Bitfield< T, LSB, MSB >::Value< TT > Class Template Reference

Internal helper type.


```
#include <bitfield>
```

Inheritance diagram for `cxx::Bitfield< T, LSB, MSB >::Value< TT >`:





Collaboration diagram for `cxx::Bitfield< T, LSB, MSB >::Value< TT >`:



### 15.11.1 Detailed Description

```

template<typename T, unsigned LSB, unsigned MSB>
template<typename TT>
class cxx::Bitfield< T, LSB, MSB >::Value< TT >

```

Internal helper type.

Definition at line 225 of file [bitfield](#).

The documentation for this class was generated from the following file:


- `I4/cxx/bitfield`

## 15.12 `cxx::Bitfield< T, LSB, MSB >::Value_base< TT >` Class Template Reference


Internal helper type.

```
#include <bitfield>
```

Inheritance diagram for `cxx::Bitfield< T, LSB, MSB >::Value_base< TT >`:



Collaboration diagram for `cxx::Bitfield< T, LSB, MSB >::Value_base< TT >`:



### 15.12.1 Detailed Description

```

template<typename T, unsigned LSB, unsigned MSB>
template<typename TT>
class cxx::Bitfield< T, LSB, MSB >::Value_base< TT >

```

Internal helper type.

Definition at line 207 of file [bitfield](#).

The documentation for this class was generated from the following file:


- `I4/cxx/bitfield`

## 15.13 `cxx::Bitfield< T, LSB, MSB >::Value_unshifted< TT >` Class Template Reference


Internal helper type.

```
#include <bitfield>
```

Inheritance diagram for `cxx::Bitfield< T, LSB, MSB >::Value_unshifted< TT >`:



Collaboration diagram for `cxx::Bitfield< T, LSB, MSB >::Value_unshifted< TT >`:



### 15.13.1 Detailed Description

```

template<typename T, unsigned LSB, unsigned MSB>
template<typename TT>
class cxx::Bitfield< T, LSB, MSB >::Value_unshifted< TT >

```

Internal helper type.

Definition at line 238 of file [bitfield](#).

The documentation for this class was generated from the following file:


- [l4/cxx/bitfield](#)

## 15.14 cxx::Bitmap< BITS > Class Template Reference


A static bitmap.

```
#include <bitmap>
```

Inheritance diagram for cxx::Bitmap< BITS >:



Collaboration diagram for `cxx::Bitmap< BITS >`:



### Public Member Functions

- **Bitmap** () noexcept  
*Create a bitmap with `BITS` bits.*
- long `scan_zero` (long start\_bit=0) const noexcept  
*Scan for the first zero bit.*

### Public Member Functions inherited from `cxx::Bitmap_base`

- void `bit` (long bit, bool on) noexcept  
*Set the value of bit `bit` to `on`.*

- void `clear_bit` (long `bit`) noexcept  
*Clear bit `bit`.*
- void `atomic_clear_bit` (long `bit`) noexcept  
*Clear bit `bit` atomically.*
- `word_type` `atomic_get_and_clear` (long `bit`) noexcept  
*Clear bit `bit` atomically and return old state.*
- void `set_bit` (long `bit`) noexcept  
*Set bit `bit`.*
- void `atomic_set_bit` (long `bit`) noexcept  
*Set bit `bit` atomically.*
- `word_type` `atomic_get_and_set` (long `bit`) noexcept  
*Set bit `bit` atomically and return old state.*
- `word_type` `bit` (long `bit`) const noexcept  
*Get the truth value of a bit.*
- `word_type` `operator[]` (long `bit`) const noexcept  
*Get the bit at index `bit`.*
- `Bit operator[]` (long `bit`) noexcept  
*Get the lvalue for the bit at index `bit`.*
- long `scan_zero` (long `max_bit`, long `start_bit=0`) const noexcept  
*Scan for the first zero bit.*

### Additional Inherited Members

### Static Public Member Functions inherited from `cxx::Bitmap_base`

- static long `words` (long `bits`) noexcept  
*Get the number of `Words` that are used for the bitmap.*
- static long `chars` (long `bits`) noexcept  
*Get the number of chars that are used for the bitmap.*

### Protected Types inherited from `cxx::Bitmap_base`

- enum { `W_bits` = sizeof(`word_type`) \* 8 , `C_bits` = 8 }
- typedef unsigned long `word_type`  
*Data type for each element of the bit buffer.*

### Static Protected Member Functions inherited from `cxx::Bitmap_base`

- static unsigned `word_index` (unsigned `bit`)  
*Get the word index for the given bit.*
- static unsigned `bit_index` (unsigned `bit`)  
*Get the bit index within `word_type` for the given bit.*

### Protected Attributes inherited from `cxx::Bitmap_base`

- `word_type` \* `_bits`  
*Pointer to the buffer storing the bits.*

### 15.14.1 Detailed Description

```
template<int BITS>
class cxx::Bitmap< BITS >
```

A static bitmap.

#### Template Parameters

<i>BITS</i>	The number of bits that shall be in the bitmap.
-------------	---

Definition at line 220 of file [bitmap](#).

### 15.14.2 Member Function Documentation

#### 15.14.2.1 scan\_zero()

```
template<int BITS>
long cxx::Bitmap< BITS >::scan_zero (
    long start_bit = 0) const [inline], [noexcept]
```

Scan for the first zero bit.

#### Parameters

<i>start_bit</i>	Hint at the number of the first bit to look at. Zero bits below <i>start_bit</i> may or may not be taken into account by the implementation.
------------------	--

#### Return values

<i>&gt;=</i>	0 Number of first zero bit found.
<i>-1</i>	All bits at <i>start_bit</i> or higher are set.

Compared to [Bitmap\\_base::scan\\_zero\(\)](#), the upper bound is set to BITS.

Definition at line 365 of file [bitmap](#).

References [cxx::Bitmap\\_base::scan\\_zero\(\)](#).

Here is the call graph for this function:



The documentation for this class was generated from the following file:


- `I4/cxx/bitmap`

## 15.15 cxx::Bitmap\_base Class Reference

Basic bitmap abstraction.

```
#include <bitmap>
```

Inheritance diagram for cxx::Bitmap\_base:





Collaboration diagram for cxx::Bitmap\_base:

cxx::Bitmap_base
# _bits
+ bit()
+ clear_bit()
+ atomic_clear_bit()
+ atomic_get_and_clear()
+ set_bit()
+ atomic_set_bit()
+ atomic_get_and_set()
+ bit()
+ operator[]()
+ operator[]()
+ scan_zero()
+ words()
+ chars()
# word_index()
# bit_index()

## Data Structures

- class [Bit](#)  
*A writable bit in a bitmap.*
- class [Word](#)  
*Helper abstraction for a word contained in the bitmap.*
- class [Char](#)  
*Helper abstraction for a byte contained in the bitmap.*

## Public Member Functions

- void [bit](#) (long bit, bool on) noexcept  
*Set the value of bit [bit](#) to on.*
- void [clear\\_bit](#) (long [bit](#)) noexcept  
*Clear bit [bit](#).*
- void [atomic\\_clear\\_bit](#) (long [bit](#)) noexcept  
*Clear bit [bit](#) atomically.*
- [word\\_type](#) [atomic\\_get\\_and\\_clear](#) (long [bit](#)) noexcept  
*Clear bit [bit](#) atomically and return old state.*

- void `set_bit` (long `bit`) noexcept  
*Set bit `bit`.*
- void `atomic_set_bit` (long `bit`) noexcept  
*Set bit `bit` atomically.*
- `word_type` `atomic_get_and_set` (long `bit`) noexcept  
*Set bit `bit` atomically and return old state.*
- `word_type` `bit` (long `bit`) const noexcept  
*Get the truth value of a bit.*
- `word_type` `operator[]` (long `bit`) const noexcept  
*Get the bit at index `bit`.*
- `Bit operator[]` (long `bit`) noexcept  
*Get the lvalue for the bit at index `bit`.*
- long `scan_zero` (long `max_bit`, long `start_bit=0`) const noexcept  
*Scan for the first zero bit.*

### Static Public Member Functions

- static long `words` (long `bits`) noexcept  
*Get the number of `Words` that are used for the bitmap.*
- static long `chars` (long `bits`) noexcept  
*Get the number of `chars` that are used for the bitmap.*

### Protected Types

- enum { `W_bits` = sizeof(`word_type`) \* 8 , `C_bits` = 8 }
- typedef unsigned long `word_type`  
*Data type for each element of the bit buffer.*

### Static Protected Member Functions

- static unsigned `word_index` (unsigned `bit`)  
*Get the word index for the given bit.*
- static unsigned `bit_index` (unsigned `bit`)  
*Get the bit index within `word_type` for the given bit.*

### Protected Attributes

- `word_type` \* `_bits`  
*Pointer to the buffer storing the bits.*

## 15.15.1 Detailed Description

Basic bitmap abstraction.

This abstraction keeps a pointer to a memory area that is used as bitmap.

Definition at line 18 of file `bitmap`.

## 15.15.2 Member Enumeration Documentation

### 15.15.2.1 anonymous enum

anonymous enum [protected]

#### Enumerator

W_bits	number of bits in <a href="#">word_type</a>
C_bits	number of bits in char

Definition at line 26 of file [bitmap](#).

## 15.15.3 Member Function Documentation

### 15.15.3.1 atomic\_clear\_bit()

```
void cxx::Bitmap_base::atomic_clear_bit (
    long bit) [inline], [noexcept]
```

Clear bit [bit](#) atomically.

Use this function for multi-threaded access to the bitmap.


#### Parameters

<i>bit</i>	The number of the bit to clear.
------------	---------------------------------

Definition at line 269 of file [bitmap](#).

References [\\_bits](#), [bit\(\)](#), [bit\\_index\(\)](#), and [word\\_index\(\)](#).

Here is the call graph for this function:



### 15.15.3.2 atomic\_get\_and\_clear()

```
Bitmap_base::word_type cxx::Bitmap_base::atomic_get_and_clear (
    long bit) [inline], [noexcept]
```

Clear bit `bit` atomically and return old state.

Use this function for multi-threaded access to the bitmap.


#### Parameters

<i>bit</i>	The number of the bit to clear.
------------	---------------------------------

Definition at line 279 of file [bitmap](#).

References [\\_bits](#), [bit\(\)](#), [bit\\_index\(\)](#), and [word\\_index\(\)](#).

Here is the call graph for this function:



### 15.15.3.3 atomic\_get\_and\_set()

```
Bitmap_base::word_type cxx::Bitmap_base::atomic_get_and_set (
    long bit) [inline], [noexcept]
```

Set bit `bit` atomically and return old state.

Use this function for multi-threaded access to the bitmap.


#### Parameters

<i>bit</i>	The number of the bit to set.
------------	-------------------------------

Definition at line 308 of file [bitmap](#).

References [\\_bits](#), [bit\(\)](#), [bit\\_index\(\)](#), and [word\\_index\(\)](#).

Here is the call graph for this function:



### 15.15.3.4 atomic\_set\_bit()

```
void cxx::Bitmap_base::atomic_set_bit (
    long bit) [inline], [noexcept]
```

Set bit *bit* atomically.

Use this function for multi-threaded access to the bitmap.


#### Parameters

<i>bit</i>	The number of the bit to set.
------------	-------------------------------

Definition at line 298 of file [bitmap](#).

References [\\_bits](#), [bit\(\)](#), [bit\\_index\(\)](#), and [word\\_index\(\)](#).

Here is the call graph for this function:



### 15.15.3.5 bit() [1/2]

```
Bitmap_base::word_type cxx::Bitmap_base::bit (
    long bit) const [inline], [noexcept]
```

Get the truth value of a bit.

#### Parameters

<i>bit</i>	The number of the bit to read.
------------	--------------------------------


#### Return values

0	Bit is not set.
!= 0	Bit is set.

Definition at line 318 of file [bitmap](#).

References [\\_bits](#), [bit\(\)](#), [bit\\_index\(\)](#), and [word\\_index\(\)](#).

Here is the call graph for this function:



### 15.15.3.6 bit() [2/2]

```
void cxx::Bitmap_base::bit (
    long bit,
    bool on) [inline], [noexcept]
```

Set the value of bit `bit` to `on`.

#### Parameters


<i>bit</i>	The number of the bit.
<i>on</i>	The boolean value that shall be assigned to the bit.

Definition at line 251 of file `bitmap`.


References `_bits`, `bit()`, `bit_index()`, and `word_index()`.

Referenced by `atomic_clear_bit()`, `atomic_get_and_clear()`, `atomic_get_and_set()`, `atomic_set_bit()`, `bit()`, `bit()`, `bit_index()`, `clear_bit()`, `operator[]()`, `operator[]()`, `set_bit()`, and `word_index()`.

Here is the call graph for this function:



Here is the caller graph for this function:



### 15.15.3.7 bit\_index()

```
unsigned cxx::Bitmap_base::bit_index (
    unsigned bit) [inline], [static], [protected]
```

Get the bit index within [word\\_type](#) for the given bit.

#### Parameters

<i>bit</i>	The bit index in the bitmap.
------------	------------------------------

#### Returns

the bit index within [word\\_type](#) ( $\text{bit} \% W\_bits$ ).

Definition at line 53 of file [bitmap](#).

References [bit\(\)](#), and [W\\_bits](#).

Referenced by [atomic\\_clear\\_bit\(\)](#), [atomic\\_get\\_and\\_clear\(\)](#), [atomic\\_get\\_and\\_set\(\)](#), [atomic\\_set\\_bit\(\)](#), [bit\(\)](#), [bit\(\)](#), [clear\\_bit\(\)](#), and [set\\_bit\(\)](#).

Here is the call graph for this function:







**15.15.3.9 operator[]() [1/2]**

```
word_type cxx::Bitmap_base::operator[] (
    long bit) const [inline], [noexcept]
```

Get the bit at index `bit`.

**Parameters**

<i>bit</i>	The number of the bit to read.
------------	--------------------------------


**Return values**

0	Bit is not set.
!= 0	Bit is set.

Definition at line 181 of file `bitmap`.

References `bit()`.

Here is the call graph for this function:

**15.15.3.10 operator[]() [2/2]**

```
Bit cxx::Bitmap_base::operator[] (
    long bit) [inline], [noexcept]
```

Get the lvalue for the bit at index `bit`.

**Parameters**

<i>bit</i>	The number.
------------	-------------


**Returns**

lvalue for [bit](#)

Definition at line 191 of file [bitmap](#).

References [bit\(\)](#).

Here is the call graph for this function:

**15.15.3.11 scan\_zero()**

```
long cxx::Bitmap_base::scan_zero (
    long max_bit,
    long start_bit = 0) const [inline], [noexcept]
```

Scan for the first zero bit.

**Parameters**

<i>max_bit</i>	Upper bound (exclusive) for the scanning operation.
<i>start_bit</i>	Hint at the number of the first bit to look at. Zero bits below <i>start_bit</i> may or may not be taken into account by the implementation.

**Return values**

<i>&gt;=</i>	0 Number of first zero bit found.
<i>-1</i>	All bits between <i>start_bit</i> and <i>max_bit</i> are set.

Definition at line 339 of file [bitmap](#).

References [\\_bits](#), [W\\_bits](#), and [word\\_index\(\)](#).

Referenced by [cxx::Bitmap< BITS >::scan\\_zero\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 15.15.3.12 set\_bit()

```
void cxx::Bitmap_base::set_bit (
    long bit) [inline], [noexcept]
```

Set bit `bit`.


#### Parameters

<i>bit</i>	The number of the bit to set.
------------	-------------------------------

Definition at line 289 of file `bitmap`.

References `_bits`, `bit()`, `bit_index()`, and `word_index()`.

Here is the call graph for this function:



### 15.15.3.13 word\_index()

```
unsigned cxx::Bitmap_base::word_index (
    unsigned bit) [inline], [static], [protected]
```

Get the word index for the given bit.

#### Parameters

<i>bit</i>	The index of the bit in question.
------------	-----------------------------------

**Returns**


the index in `Bitmap_base::_bits` for the given bit (`bit / W_bits`).

Definition at line 44 of file `bitmap`.


References `bit()`, and `W_bits`.

Referenced by `atomic_clear_bit()`, `atomic_get_and_clear()`, `atomic_get_and_set()`, `atomic_set_bit()`, `bit()`, `bit()`, `clear_bit()`, `scan_zero()`, and `set_bit()`.

Here is the call graph for this function:



Here is the caller graph for this function:



The documentation for this class was generated from the following file:


- `I4/cxx/bitmap`

## 15.16 cxx::Bitmap\_base::Bit Class Reference

A writable bit in a bitmap.

```
#include <bitmap>
```

Collaboration diagram for cxx::Bitmap\_base::Bit:



### 15.16.1 Detailed Description

A writable bit in a bitmap.

Definition at line 58 of file [bitmap](#).

The documentation for this class was generated from the following file:


- I4/cxx/bitmap

## 15.17 cxx::Bitmap\_base::Char< BITS > Class Template Reference

Helper abstraction for a byte contained in the bitmap.

```
#include <bitmap>
```

Collaboration diagram for cxx::Bitmap\_base::Char< BITS >:



### 15.17.1 Detailed Description

```
template<long BITS>
class cxx::Bitmap_base::Char< BITS >
```

Helper abstraction for a byte contained in the bitmap.

Definition at line 95 of file [bitmap](#).

The documentation for this class was generated from the following file:


- I4/cxx/bitmap

## 15.18 cxx::Bitmap\_base::Word< BITS > Class Template Reference


Helper abstraction for a word contained in the bitmap.

```
#include <bitmap>
```

Inheritance diagram for cxx::Bitmap\_base::Word< BITS >:



Collaboration diagram for cxx::Bitmap\_base::Word< BITS >:



### 15.18.1 Detailed Description

```
template<long BITS>
class cxx::Bitmap_base::Word< BITS >
```

Helper abstraction for a word contained in the bitmap.

Definition at line 79 of file [bitmap](#).

The documentation for this class was generated from the following file:

- I4/cxx/bitmap

## 15.19 cxx::Bits::Avl\_map\_get\_key< KEY\_TYPE > Struct Template Reference

Key-getter for [Avl\\_map](#).

```
#include <avl_map>
```

Collaboration diagram for cxx::Bits::Avl\_map\_get\_key< KEY\_TYPE >:



### 15.19.1 Detailed Description

```
template<typename KEY_TYPE>
struct cxx::Bits::Avl_map_get_key< KEY_TYPE >
```

Key-getter for [Avl\\_map](#).

Definition at line 25 of file [avl\\_map](#).

The documentation for this struct was generated from the following file:


- I4/cxx/[avl\\_map](#)

## 15.20 `cxx::Bits::Avl_set_get_key< KEY_TYPE >` Struct Template Reference

Internal, key-getter for [Avl\\_set](#) nodes.

```
#include <avl_set>
```

Collaboration diagram for `cxx::Bits::Avl_set_get_key< KEY_TYPE >`:



```

classDiagram
    class cxx_Bits_Avl_set_get_key_["cxx::Bits::Avl_set_get_key< KEY_TYPE >"]
    
```

### 15.20.1 Detailed Description

```
template<typename KEY_TYPE>
struct cxx::Bits::Avl_set_get_key< KEY_TYPE >
```

Internal, key-getter for [Avl\\_set](#) nodes.

Definition at line [103](#) of file [avl\\_set](#).

The documentation for this struct was generated from the following file:

- [l4/cxx/avl\\_set](#)


## 15.21 `cxx::Bits::Avl_set_iter< Node, Key, Node_op >` Class Template Reference

Generic iterator for the AVL-tree based set.


```
#include <avl_set>
```



Inheritance diagram for cxx::Bits::Avl\_set\_iter< Node, Key, Node\_op >:



Collaboration diagram for cxx::Bits::Avl\_set\_iter< Node, Key, Node\_op >:



## Public Member Functions

- `Avl_set_iter()`=default  
Create an invalid iterator (end marker).

- [Avl\\_set\\_iter](#) (Node const \*t)  
*Create an iterator for the given tree.*
- [Avl\\_set\\_iter](#) (Base const &o)  
*Create an iterator from a BST iterator.*
- [Avl\\_set\\_iter](#) (Non\_const\_iter const &o)  
*Allow copy of non-const iterator to const iterator versions.*
- [Avl\\_set\\_iter](#) & [operator=](#) (Non\_const\_iter const &o)  
*Allow assignment of non-const iterator to const iterator versions.*
- Key & [operator\\*](#) () const  
*Dereference the iterator and get the item out of the tree.*
- Key \* [operator->](#) () const  
*Member access to the item the iterator points to.*
- [Avl\\_set\\_iter](#) & [operator++](#) ()  
*Set the iterator to the next element (pre increment).*
- [Avl\\_set\\_iter](#) [operator++](#) (int)  
*Set the iterator to the next element (post increment).*

### 15.21.1 Detailed Description

```
template<typename Node, typename Key, typename Node_op>
class cxx::Bits::Avl_set_iter< Node, Key, Node_op >
```

Generic iterator for the AVL-tree based set.

Definition at line 35 of file [avl\\_set](#).

### 15.21.2 Constructor & Destructor Documentation

#### 15.21.2.1 Avl\_set\_iter() [1/2]

```
template<typename Node, typename Key, typename Node_op>
cxx::Bits::Avl_set_iter< Node, Key, Node_op >::Avl_set_iter (
    Node const * t) [inline]
```

Create an iterator for the given tree.

#### Parameters

<i>t</i>	the root node of the tree to iterate.
----------	---------------------------------------

Definition at line 59 of file [avl\\_set](#).

### 15.21.2.2 Avl\_set\_iter() [2/2]

```
template<typename Node, typename Key, typename Node_op>
cxx::Bits::Avl_set_iter< Node, Key, Node_op >::Avl_set_iter (
    Base const & o) [inline]
```

Create an iterator from a BST iterator.

#### Parameters

<i>o</i>	The BST iterator that shall be copied.
----------	--

Definition at line 65 of file [avl\\_set](#).

## 15.21.3 Member Function Documentation

### 15.21.3.1 operator\*()

```
template<typename Node, typename Key, typename Node_op>
Key & cxx::Bits::Avl_set_iter< Node, Key, Node_op >::operator* () const [inline]
```

Dereference the iterator and get the item out of the tree.

#### Returns

A reference to the data stored in the AVL tree.

Definition at line 80 of file [avl\\_set](#).

### 15.21.3.2 operator->()

```
template<typename Node, typename Key, typename Node_op>
Key * cxx::Bits::Avl_set_iter< Node, Key, Node_op >::operator-> () const [inline]
```

Member access to the item the iterator points to.

#### Returns

A pointer to the item in the node.

Definition at line 87 of file [avl\\_set](#).

The documentation for this class was generated from the following file:


- [I4/cxx/avl\\_set](#)

## 15.22 cxx::Bits::Base\_avl\_set< ITEM\_TYPE, COMPARE, ALLOC, GET\_KEY > Class Template Reference

AVL set with internally managed nodes.

```
#include <avl_set>
```

Inheritance diagram for cxx::Bits::Base\_avl\_set< ITEM\_TYPE, COMPARE, ALLOC, GET\_KEY >:



Collaboration diagram for `cxx::Bits::Base_avl_set< ITEM_TYPE, COMPARE, ALLOC, GET_KEY >`:

<code>cxx::Bits::Base_avl_set&lt; ITEM_TYPE, COMPARE, ALLOC, GET_KEY &gt;</code>
<ul style="list-style-type: none"> <li>+ <code>Base_avl_set()</code></li> <li>+ <code>Base_avl_set()</code></li> <li>+ <code>operator=()</code></li> <li>+ <code>insert()</code></li> <li>+ <code>emplace()</code></li> <li>+ <code>clear()</code></li> <li>+ <code>remove()</code></li> <li>+ <code>erase()</code></li> <li>+ <code>find_node()</code></li> <li>+ <code>lower_bound_node()</code></li> <li>and 8 more...</li> </ul>

## Data Structures

- class [Node](#)  
A smart pointer to a tree item.

## Public Types

- enum { `E_noent` = 2 , `E_exist` = 17 , `E_nomem` = 12 , `E_inval` = 22 }  
Return status constants.
- typedef `ITEM_TYPE` **Item\_type**  
Type for the items store in the set.
- typedef `GET_KEY` **Get\_key**  
Key-getter type to derive the sort key of an internal node.
- typedef `GET_KEY::Key_type` **Key\_type**  
Type of the sort key used for the items.
- typedef `Type_traits< Item\_type >::Const_type` **Const\_item\_type**  
Type used for const items within the set.
- typedef `COMPARE` **Item\_compare**  
Type for the comparison functor.
- typedef `ALLOC< _Node >` **Node\_allocator**  
Type for the node allocator.
- typedef `Avl_set_iter< _Node, Item\_type, Fwd >` **Iterator**

- Forward iterator for the set.*
- typedef `Avl_set_iter`< `_Node`, `Const_item_type`, `Fwd` > **`Const_iterator`**  
*Constant forward iterator for the set.*
- typedef `Avl_set_iter`< `_Node`, `Item_type`, `Rev` > **`Rev_iterator`**  
*Backward iterator for the set.*
- typedef `Avl_set_iter`< `_Node`, `Const_item_type`, `Rev` > **`Const_rev_iterator`**  
*Constant backward iterator for the set.*

## Public Member Functions

- `Base_avl_set` (`Node_allocator` const &alloc=`Node_allocator`())  
*Create a AVL-tree based set.*
- `Base_avl_set` (`Base_avl_set` const &o, `Node_allocator` const &alloc=`Node_allocator`())  
*Create a copy of an AVL-tree based set.*
- `Base_avl_set` & `operator=` (`Base_avl_set` const &o)  
*Copy assignment operator of an AVL-tree based set.*
- `cxx::Pair`< `Iterator`, `int` > `insert` (`Item_type` const &item)  
*Insert an item into the set.*
- template<typename... Args>  
`cxx::Pair`< `Iterator`, `int` > `emplace` (`Args` &&... args)  
*Eplace an item into the set.*
- void **`clear`** () noexcept  
*Remove all items from the set.*
- int `remove` (`Key_type` const &item)  
*Remove an item from the set.*
- int `erase` (`Key_type` const &item)  
*Erase the item with the given key.*
- `Node` `find_node` (`Key_type` const &item) const  
*Lookup a node equal to `item`.*
- `Node` `lower_bound_node` (`Key_type` const &key) const  
*Find the first node greater or equal to `key`.*
- `Const_iterator` `begin` () const  
*Get the constant forward iterator for the first element in the set.*
- `Const_iterator` `end` () const  
*Get the end marker for the constant forward iterator.*
- `Iterator` `begin` ()  
*Get the mutable forward iterator for the first element of the set.*
- `Iterator` `end` ()  
*Get the end marker for the mutable forward iterator.*
- `Const_rev_iterator` `rbegin` () const  
*Get the constant backward iterator for the last element in the set.*
- `Const_rev_iterator` `rend` () const  
*Get the end marker for the constant backward iterator.*
- `Rev_iterator` `rbegin` ()  
*Get the mutable backward iterator for the last element of the set.*
- `Rev_iterator` `rend` ()  
*Get the end marker for the mutable backward iterator.*

### 15.22.1 Detailed Description

```
template<typename ITEM_TYPE, class COMPARE, template< typename A > class ALLOC, typename
GET_KEY>
```

```
class cxx::Bits::Base_avl_set< ITEM_TYPE, COMPARE, ALLOC, GET_KEY >
```

AVL set with internally managed nodes.

Definition at line 127 of file [avl\\_set](#).

### 15.22.2 Member Enumeration Documentation

#### 15.22.2.1 anonymous enum

```
template<typename ITEM_TYPE, class COMPARE, template< typename A > class ALLOC, typename
GET_KEY>
```

```
anonymous enum
```

Return status constants.

These constants are compatible with the [L4](#) error codes, see [l4\\_error\\_code\\_t](#).

#### Enumerator

<code>E_noent</code>	Item does not exist.
<code>E_exist</code>	Item exists already.
<code>E_nomem</code>	Memory allocation failed.
<code>E_inval</code>	Internal error.

Definition at line 138 of file [avl\\_set](#).

### 15.22.3 Constructor & Destructor Documentation

#### 15.22.3.1 `Base_avl_set()` [1/2]

```
template<typename ITEM_TYPE, class COMPARE, template< typename A > class ALLOC, typename
GET_KEY>
```

```
cxx::Bits::Base_avl_set< ITEM_TYPE, COMPARE, ALLOC, GET_KEY >::Base_avl_set (
    Node_allocator const & alloc = Node_allocator()) [inline], [explicit]
```

Create a AVL-tree based set.

#### Parameters

<i>alloc</i>	<a href="#">Node</a> allocator.
--------------	---------------------------------

Create an empty set (AVL-tree based).

Definition at line 268 of file [avl\\_set](#).

### 15.22.3.2 Base\_avl\_set() [2/2]

```
template<typename ITEM_TYPE, class COMPARE, template< typename A > class ALLOC, typename
GET_KEY>
cxx::Bits::Base_avl_set< ITEM_TYPE, COMPARE, ALLOC, GET_KEY >::Base_avl_set (
    Base_avl_set< ITEM_TYPE, COMPARE, ALLOC, GET_KEY > const & o,
    Node_allocator const & alloc = Node_allocator()) [inline]
```

Create a copy of an AVL-tree based set.

#### Parameters

<i>o</i>	The set to copy.
<i>alloc</i>	<a href="#">Node</a> allocator.

Creates a deep copy of the set with all its items.

Definition at line [283](#) of file [avl\\_set](#).

## 15.22.4 Member Function Documentation

### 15.22.4.1 begin() [1/2]

```
template<typename ITEM_TYPE, class COMPARE, template< typename A > class ALLOC, typename
GET_KEY>
Iterator cxx::Bits::Base_avl_set< ITEM_TYPE, COMPARE, ALLOC, GET_KEY >::begin () [inline]
```

Get the mutable forward iterator for the first element of the set.

#### Returns

The mutable forward iterator for the first element of the set.

Definition at line [431](#) of file [avl\\_set](#).

### 15.22.4.2 begin() [2/2]

```
template<typename ITEM_TYPE, class COMPARE, template< typename A > class ALLOC, typename
GET_KEY>
Const_iterator cxx::Bits::Base_avl_set< ITEM_TYPE, COMPARE, ALLOC, GET_KEY >::begin () const
[inline]
```

Get the constant forward iterator for the first element in the set.

#### Returns

Constant forward iterator for the first element in the set.

Definition at line [417](#) of file [avl\\_set](#).



### 15.22.4.3 `emplace()`

```
template<typename ITEM_TYPE, class COMPARE, template< typename A > class ALLOC, typename
GET_KEY>
template<typename... Args>
cxx::Pair< Iterator, int > cxx::Bits::Base_avl_set< ITEM_TYPE, COMPARE, ALLOC, GET_KEY >←
::emplace (
    Args &&... args)
```

Emplace an item into the set.

#### Parameters

<code>args</code>	Constructor arguments for the item constructor.
-------------------	---

#### Returns

A pair of iterator (`first`) and return value (`second`). `second` will be 0 if the element was inserted into the set and `−#E_exist` if the element was already in the set and the set was therefore not updated. In both cases, `first` contains an iterator that points to the element. `second` may also be `−#E_nomem` when memory for the node could not be allocated. `first` is then invalid.

The element will always be constructed, even if there is already an existing element in the set. In case of such a collision the newly created element will then be immediately destructed.

### 15.22.4.4 `end()` [1/2]

```
template<typename ITEM_TYPE, class COMPARE, template< typename A > class ALLOC, typename
GET_KEY>
Iterator cxx::Bits::Base_avl_set< ITEM_TYPE, COMPARE, ALLOC, GET_KEY >::end () [inline]
```

Get the end marker for the mutable forward iterator.

#### Returns

The end marker for mutable forward iterator.

Definition at line 438 of file `avl_set`.

### 15.22.4.5 `end()` [2/2]

```
template<typename ITEM_TYPE, class COMPARE, template< typename A > class ALLOC, typename
GET_KEY>
Const_iterator cxx::Bits::Base_avl_set< ITEM_TYPE, COMPARE, ALLOC, GET_KEY >::end () const
[inline]
```

Get the end marker for the constant forward iterator.


**Returns**

The end marker for the constant forward iterator.

Definition at line 424 of file [avl\\_set](#).

Referenced by [insert\(\)](#).

Here is the caller graph for this function:

**15.22.4.6 erase()**

```

template<typename ITEM_TYPE, class COMPARE, template< typename A > class ALLOC, typename
GET_KEY>
int cxx::Bits::Base_avl_set< ITEM_TYPE, COMPARE, ALLOC, GET_KEY >::erase (
    Key_type const & item) [inline]
  
```

Erase the item with the given key.

**Parameters**

<i>item</i>	The key of the item to remove.
-------------	--------------------------------

Definition at line 384 of file [avl\\_set](#).

**15.22.4.7 find\_node()**

```

template<typename ITEM_TYPE, class COMPARE, template< typename A > class ALLOC, typename
GET_KEY>
Node cxx::Bits::Base_avl_set< ITEM_TYPE, COMPARE, ALLOC, GET_KEY >::find_node (
    Key_type const & item) const [inline]
  
```

Lookup a node equal to *item*.

**Parameters**

<i>item</i>	The value to search for.
-------------	--------------------------

**Returns**

A smart pointer to the element found. If no element was found the smart pointer will be invalid.

Definition at line 395 of file [avl\\_set](#).

## 15.22.4.8 insert()

```
template<typename ITEM_TYPE, class COMPARE, template< typename A > class ALLOC, typename
GET_KEY>
Pair< typename Base_avl_set< Item, Compare, Alloc, KEY_TYPE >::Iterator, int > cxx::Bits::Base_avl_set<
Item, Compare, Alloc, KEY_TYPE >::insert (
    Item_type const & item)
```

Insert an item into the set.

## Parameters

<i>item</i>	The item to insert.
-------------	---------------------

## Returns


A pair of iterator (*first*) and return value (*second*). *second* will be 0 if the element was inserted into the set and `−#E_exist` if the element was already in the set and the set was therefore not updated. In both cases, *first* contains an iterator that points to the element. *second* may also be `−#E_nomem` when memory for the node could not be allocated. *first* is then invalid.

Insert a new item into the set, each item can only be once in the set.

Definition at line 485 of file [avl\\_set](#).

References [E\\_exist](#), [E\\_nomem](#), [end\(\)](#), [cxx::Pair< First, Second >::first](#), and [cxx::Pair< First, Second >::second](#).

Here is the call graph for this function:



## 15.22.4.9 lower\_bound\_node()

```
template<typename ITEM_TYPE, class COMPARE, template< typename A > class ALLOC, typename
GET_KEY>
Node cxx::Bits::Base_avl_set< ITEM_TYPE, COMPARE, ALLOC, GET_KEY >::lower_bound_node (
    Key_type const & key) const [inline]
```

Find the first node greater or equal to *key*.

**Parameters**

<i>key</i>	Minimum key to look for.
------------	--------------------------

**Returns**

Smart pointer to the first node greater or equal to *key*. Will be invalid if no such element was found.

Definition at line 406 of file [avl\\_set](#).

**15.22.4.10 operator=()**

```
template<typename ITEM_TYPE, class COMPARE, template< typename A > class ALLOC, typename
GET_KEY>
Base_avl_set & cxx::Bits::Base_avl_set< ITEM_TYPE, COMPARE, ALLOC, GET_KEY >::operator= (
    Base_avl_set< ITEM_TYPE, COMPARE, ALLOC, GET_KEY > const & o) [inline]
```

Copy assignment operator of an AVL-tree based set.

**Parameters**

<i>o</i>	The set to copy-assign.
----------	-------------------------

Creates a deep copy of the set with all its items.

Definition at line 295 of file [avl\\_set](#).

**15.22.4.11 rbegin() [1/2]**

```
template<typename ITEM_TYPE, class COMPARE, template< typename A > class ALLOC, typename
GET_KEY>
Rev_iterator cxx::Bits::Base_avl_set< ITEM_TYPE, COMPARE, ALLOC, GET_KEY >::rbegin () [inline]
```

Get the mutable backward iterator for the last element of the set.

**Returns**

The mutable backward iterator for the last element of the set.

Definition at line 459 of file [avl\\_set](#).

**15.22.4.12 rbegin() [2/2]**

```
template<typename ITEM_TYPE, class COMPARE, template< typename A > class ALLOC, typename
GET_KEY>
Const_rev_iterator cxx::Bits::Base_avl_set< ITEM_TYPE, COMPARE, ALLOC, GET_KEY >::rbegin ()
const [inline]
```

Get the constant backward iterator for the last element in the set.

**Returns**

The constant backward iterator for the last element in the set.

Definition at line 445 of file [avl\\_set](#).

## 15.22.4.13 remove()

```
template<typename ITEM_TYPE, class COMPARE, template< typename A > class ALLOC, typename
GET_KEY>
int cxx::Bits::Base_avl_set< ITEM_TYPE, COMPARE, ALLOC, GET_KEY >::remove (
    Key_type const & item) [inline]
```

Remove an item from the set.

## Parameters

<i>item</i>	The item to remove.
-------------	---------------------


## Return values

0	Success
-E_noent	Item does not exist

Definition at line 366 of file [avl\\_set](#).

Referenced by [cxx::Bits::Base\\_avl\\_set< Local\\_item\\_type, COMPARE< KEY\\_TYPE >, ALLOC, Bits::Avl\\_map\\_get\\_key< KEY\\_TYPE](#)

Here is the caller graph for this function:



## 15.22.4.14 rend() [1/2]

```
template<typename ITEM_TYPE, class COMPARE, template< typename A > class ALLOC, typename
GET_KEY>
Rev_iterator cxx::Bits::Base_avl_set< ITEM_TYPE, COMPARE, ALLOC, GET_KEY >::rend () [inline]
```

Get the end marker for the mutable backward iterator.

## Returns

The end marker for mutable backward iterator.

Definition at line 466 of file [avl\\_set](#).

**15.22.4.15** `rend()` [2/2]

```
template<typename ITEM_TYPE, class COMPARE, template< typename A > class ALLOC, typename
GET_KEY>
Const_rev_iterator cxx::Bits::Base_avl_set< ITEM_TYPE, COMPARE, ALLOC, GET_KEY >::rend ()
const [inline]
```

Get the end marker for the constant backward iterator.

**Returns**

The end marker for the constant backward iterator.

Definition at line [452](#) of file [avl\\_set](#).

The documentation for this class was generated from the following file:

- [l4/cxx/avl\\_set](#)

**15.23** `cxx::Bits::Base_avl_set< ITEM_TYPE, COMPARE, ALLOC, GET_KEY >::Node` Class Reference

A smart pointer to a tree item.

```
#include <avl_set>
```

Collaboration diagram for `cxx::Bits::Base_avl_set< ITEM_TYPE, COMPARE, ALLOC, GET_KEY >::Node`:

cxx::Bits::Base_avl _set< ITEM_TYPE, COMPARE, ALLOC, GET_KEY >::Node	
+	Node()
+	operator*()
+	operator->()
+	valid()
+	operator Item_type const *()

## Public Member Functions

- **Node** ()  
*Default construction for NIL pointer.*
- `Item_type` const & **operator\*** ()  
*Dereference the pointer.*
- `Item_type` const \* **operator->** ()  
*Dereferenced member access.*
- bool **valid** () const  
*Validity check.*
- **operator** `Item_type` const \* ()  
*Cast to a real item pointer.*

### 15.23.1 Detailed Description

```
template<typename ITEM_TYPE, class COMPARE, template< typename A > class ALLOC, typename
GET_KEY>
class cxx::Bits::Base_avl_set< ITEM_TYPE, COMPARE, ALLOC, GET_KEY >::Node
```

A smart pointer to a tree item.

Definition at line 182 of file `avl_set`.

### 15.23.2 Member Function Documentation

#### 15.23.2.1 `operator*()`

```
template<typename ITEM_TYPE, class COMPARE, template< typename A > class ALLOC, typename
GET_KEY>
Item_type const & cxx::Bits::Base_avl_set< ITEM_TYPE, COMPARE, ALLOC, GET_KEY >::Node::operator*
() [inline]
```

Dereference the pointer.

#### Precondition

`Node` is valid.

Definition at line 200 of file `avl_set`.

#### 15.23.2.2 `operator->()`

```
template<typename ITEM_TYPE, class COMPARE, template< typename A > class ALLOC, typename
GET_KEY>
Item_type const * cxx::Bits::Base_avl_set< ITEM_TYPE, COMPARE, ALLOC, GET_KEY >::Node::operator->
() [inline]
```

Dereferenced member access.

#### Precondition

`Node` is valid.

Definition at line 207 of file `avl_set`.





Collaboration diagram for cxx::Bits::Basic\_list< POLICY >:

cxx::Bits::Basic_list < POLICY >	
#	_f
+	empty()
+	front()
+	clear()
+	begin()
+	begin()
+	end()
+	end()
+	iter()

### Public Member Functions

- bool **empty** () const  
*Check if the list is empty.*
- Value\_type **front** () const  
*Return the first element in the list.*
- void **clear** ()  
*Remove all elements from the list.*
- Iterator **begin** ()  
*Return an iterator to the beginning of the list.*
- Const\_iterator **begin** () const  
*Return a const iterator to the beginning of the list.*
- Const\_iterator **end** () const  
*Return a const iterator to the end of the list.*
- Iterator **end** ()  
*Return an iterator to the end of the list.*

### Static Public Member Functions

- static Const\_iterator **iter** (Const\_value\_type c)  
*Return a const iterator that begins at the given element.*

### Protected Attributes

- POLICY::Head\_type **\_f**  
*Pointer to front of the list.*

### 15.24.1 Detailed Description

```
template<typename POLICY>
class cxx::Bits::Basic_list< POLICY >
```

Internal: Common functions for all head-based list implementations.

Definition at line 39 of file [list\\_basics.h](#).

### 15.24.2 Member Function Documentation

#### 15.24.2.1 clear()

```
template<typename POLICY>
void cxx::Bits::Basic_list< POLICY >::clear () [inline]
```

Remove all elements from the list.

After the operation the state of the elements is undefined.

Definition at line 135 of file [list\\_basics.h](#).

References [\\_f](#).

#### 15.24.2.2 iter()

```
template<typename POLICY>
Const_iterator cxx::Bits::Basic_list< POLICY >::iter (
    Const_value_type c) [inline], [static]
```

Return a const iterator that begins at the given element.

#### Parameters

<i>c</i>	Element where the iterator should start.
----------	--

#### Precondition

The element *c* must already be in a list.

Definition at line 148 of file [list\\_basics.h](#).

The documentation for this class was generated from the following file:


- I4/cxx/bits/list\_basics.h

## 15.25 cxx::Bits::Bst< Node, Get\_key, Compare > Class Template Reference


Basic binary search tree (BST).

```
#include <bst.h>
```

Inheritance diagram for cxx::Bits::Bst< Node, Get\_key, Compare >:



Collaboration diagram for `cxx::Bits::Bst< Node, Get_key, Compare >`:



## Public Types

- `typedef Get_key::Key_type Key_type`  
*The type of key values used to generate the total order of the elements.*
- `typedef Type_traits< Key\_type >::Param_type Key_param_type`  
*The type for key parameters.*
- `typedef Fwd Fwd_iter_ops`

*Helper for building forward iterators for different wrapper classes.*

- typedef Rev **Rev\_iter\_ops**

*Helper for building reverse iterators for different wrapper classes.*

### Iterators

- typedef \_\_Bst\_iter< Node, Node, Fwd > **Iterator**  
*Forward iterator.*
- typedef \_\_Bst\_iter< Node, Node const, Fwd > **Const\_iterator**  
*Constant forward iterator.*
- typedef \_\_Bst\_iter< Node, Node, Rev > **Rev\_iterator**  
*Backward iterator.*
- typedef \_\_Bst\_iter< Node, Node const, Rev > **Const\_rev\_iterator**  
*Constant backward.*

### Public Member Functions

#### Get default iterators for the ordered tree.

- [Const\\_iterator begin](#) () const  
*Get the constant forward iterator for the first element in the set.*
- [Const\\_iterator end](#) () const  
*Get the end marker for the constant forward iterator.*
- [Iterator begin](#) ()  
*Get the mutable forward iterator for the first element of the set.*
- [Iterator end](#) ()  
*Get the end marker for the mutable forward iterator.*
- [Const\\_rev\\_iterator rbegin](#) () const  
*Get the constant backward iterator for the last element in the set.*
- [Const\\_rev\\_iterator rend](#) () const  
*Get the end marker for the constant backward iterator.*
- [Rev\\_iterator rbegin](#) ()  
*Get the mutable backward iterator for the last element of the set.*
- [Rev\\_iterator rend](#) ()  
*Get the end marker for the mutable backward iterator.*

#### Lookup functions.

- Node \* [find\\_node](#) (Key\_param\_type key) const  
*find the node with the given key.*
- Node \* [lower\\_bound\\_node](#) (Key\_param\_type key) const  
*Find the first node with a key not less than the given key.*
- [Const\\_iterator find](#) (Key\_param\_type key) const  
*find the node with the given key.*
- template<typename FUNC>  
void [remove\\_all](#) (FUNC &&callback)  
*Clear the tree.*

### Static Protected Member Functions

- template<typename FUNC>  
static void [remove\\_tree](#) (Bst\_node \*head, FUNC &&callback)  
*Remove all elements in the subtree of head.*

### Interior access for descendants.

As this class is an intended base class we provide protected access to our interior, use 'using' to make this private in concrete implementations.

- `Bst_node * _head`  
*The head pointer of the tree.*
- `Bst ()`  
*Create an empty tree.*
- `Node * head () const`  
*Access the head node as object of type Node.*
- `static Key_type k (Bst_node const *n)`  
*Get the key value of n.*
- `static Dir dir (Key_param_type l, Key_param_type r)`  
*Get the direction to go from l to search for r.*
- `static Dir dir (Key_param_type l, Bst_node const *r)`  
*Get the direction to go from l to search for r.*
- `static bool greater (Key_param_type l, Key_param_type r)`  
*Is l greater than r.*
- `static bool greater (Key_param_type l, Bst_node const *r)`  
*Is l greater than r.*
- `static bool greater (Bst_node const *l, Bst_node const *r)`  
*Is l greater than r.*

## 15.25.1 Detailed Description

```
template<typename Node, typename Get_key, typename Compare>
class cxx::Bits::Bst< Node, Get_key, Compare >
```

Basic binary search tree (BST).

This class is intended as a base class for concrete binary search trees, such as an AVL tree. This class already provides the basic lookup methods and iterator definitions for a BST.

Definition at line 31 of file [bst.h](#).

## 15.25.2 Member Function Documentation

### 15.25.2.1 begin() [1/2]

```
template<typename Node, typename Get_key, typename Compare>
Iterator cxx::Bits::Bst< Node, Get_key, Compare >::begin () [inline]
```

Get the mutable forward iterator for the first element of the set.

**Returns**

The mutable forward iterator for the first element of the set.

Definition at line 184 of file [bst.h](#).

References [head\(\)](#).

Here is the call graph for this function:

**15.25.2.2 `begin()` [2/2]**

```
template<typename Node, typename Get_key, typename Compare>
Const_iterator cxx::Bits::Bst< Node, Get_key, Compare >::begin () const [inline]
```

Get the constant forward iterator for the first element in the set.

**Returns**

Constant forward iterator for the first element in the set.

Definition at line 173 of file [bst.h](#).

References [head\(\)](#).

Here is the call graph for this function:



### 15.25.2.3 `dir()` [1/2]

```
template<typename Node, typename Get_key, typename Compare>
Dir cxx::Bits::Bst< Node, Get_key, Compare >::dir (
    Key_param_type l,
    Bst_node const * r) [inline], [static], [protected]
```

Get the direction to go from `l` to search for `r`.

#### Parameters

<code>l</code>	is the key to look for.
<code>r</code>	is the node at the current position.


#### Return values

<code>Direction::L</code>	For left.
<code>Direction::R</code>	For right.
<code>Direction::N</code>	If <code>l</code> is equal to <code>r</code> .

Definition at line 129 of file `bst.h`.

References `dir()`, and `k()`.

Here is the call graph for this function:



### 15.25.2.4 `dir()` [2/2]

```
template<typename Node, typename Get_key, typename Compare>
Dir cxx::Bits::Bst< Node, Get_key, Compare >::dir (
    Key_param_type l,
    Key_param_type r) [inline], [static], [protected]
```

Get the direction to go from `l` to search for `r`.



**Parameters**

<i>l</i>	is the key to look for.
<i>r</i>	is the key at the current position.

**Return values**


<a href="#"><code>Direction::L</code></a>	for left
<a href="#"><code>Direction::R</code></a>	for right
<a href="#"><code>Direction::N</code></a>	if <code>l</code> is equal to <code>r</code> .

Definition at line 112 of file [bst.h](#).

References [`cxx::Bits::Direction::L`](#), and [`cxx::Bits::Direction::N`](#).

Referenced by [dir\(\)](#), [find\(\)](#), [find\\_node\(\)](#), [cxx::Avl\\_tree< Node, Get\\_key, Compare >::insert\(\)](#), [lower\\_bound\\_node\(\)](#), and [cxx::Avl\\_tree< Node, Get\\_key, Compare >::remove\(\)](#).

Here is the caller graph for this function:

**15.25.2.5 end() [1/2]**

```
template<typename Node, typename Get_key, typename Compare>
Iterator cxx::Bits::Bst< Node, Get_key, Compare >::end () [inline]
```

Get the end marker for the mutable forward iterator.

**Returns**

The end marker for mutable forward iterator.

Definition at line 189 of file [bst.h](#).

### 15.25.2.6 end() [2/2]

```
template<typename Node, typename Get_key, typename Compare>
Const_iterator cxx::Bits::Bst< Node, Get_key, Compare >::end () const [inline]
```

Get the end marker for the constant forward iterator.

#### Returns

The end marker for the constant forward iterator.

Definition at line 178 of file [bst.h](#).

### 15.25.2.7 find()

```
template<typename Node, typename Get_key, class Compare>
Bst< Node, Get_key, Compare >::Const_iterator cxx::Bits::Bst< Node, Get_key, Compare >::find
(
    Key_param_type key) const [inline]
```

find the node with the given *key*.

#### Parameters

<i>key</i>	The key value of the element to search.
------------	---

#### Returns

A valid iterator for the node with the given *key*, or an invalid iterator if *key* was not found.

Definition at line 306 of file [bst.h](#).

References [\\_head](#), [dir\(\)](#), [cxx::Bits::Direction::L](#), [cxx::Bits::Direction::N](#), and [cxx::Bits::Bst\\_node::next\(\)](#).

Here is the call graph for this function:



### 15.25.2.8 `find_node()`

```
template<typename Node, typename Get_key, class Compare>
Node * cxx::Bits::Bst< Node, Get_key, Compare >::find_node (
    Key_param_type key) const [inline]
```

find the node with the given *key*.

#### Parameters

<i>key</i>	The key value of the element to search.
------------	---


#### Returns

A pointer to the node with the given *key*, or NULL if *key* was not found.

Definition at line 270 of file `bst.h`.

References `_head`, `dir()`, `cxx::Bits::Direction::N`, and `cxx::Bits::Bst_node::next()`.

Here is the call graph for this function:



### 15.25.2.9 `lower_bound_node()`

```
template<typename Node, typename Get_key, class Compare>
Node * cxx::Bits::Bst< Node, Get_key, Compare >::lower_bound_node (
    Key_param_type key) const [inline]
```

Find the first node with a key not less than the given *key*.

#### Parameters

<i>key</i>	The key used for the search.
------------	------------------------------


**Returns**

A pointer to the found node, or `NULL` if no node was found.

Definition at line 286 of file [bst.h](#).

References [\\_head](#), [dir\(\)](#), [cxx::Bits::Direction::L](#), [cxx::Bits::Direction::N](#), and [cxx::Bits::Bst\\_node::next\(\)](#).

Here is the call graph for this function:

**15.25.2.10 rbegin() [1/2]**

```
template<typename Node, typename Get_key, typename Compare>
Rev_iterator cxx::Bits::Bst< Node, Get_key, Compare >::rbegin () [inline]
```

Get the mutable backward iterator for the last element of the set.

**Returns**

The mutable backward iterator for the last element of the set.

Definition at line 206 of file [bst.h](#).

References [head\(\)](#).

Here is the call graph for this function:



**15.25.2.11** `rbegin()` [2/2]

```
template<typename Node, typename Get_key, typename Compare>
Const_rev_iterator cxx::Bits::Bst< Node, Get_key, Compare >::rbegin () const [inline]
```

Get the constant backward iterator for the last element in the set.

**Returns**

The constant backward iterator for the last element in the set.

Definition at line 195 of file [bst.h](#).

References [head\(\)](#).

Here is the call graph for this function:

**15.25.2.12** `remove_all()`

```
template<typename Node, typename Get_key, typename Compare>
template<typename FUNC>
void cxx::Bits::Bst< Node, Get_key, Compare >::remove_all (
    FUNC && callback) [inline]
```

Clear the tree.

**Parameters**

<i>callback</i>	Optional function to be called on each removed element.
-----------------	---


The callback may delete the elements. The function guarantees that the elements are no longer used after the callback has been called.

Definition at line 252 of file [bst.h](#).


References [\\_head](#), [head\(\)](#), and [remove\\_tree\(\)](#).

Referenced by [cxx::Avl\\_tree< Entry, Names\\_get\\_key >::~~Avl\\_tree\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 15.25.2.13 remove\_tree()

```

template<typename Node, typename Get_key, typename Compare>
template<typename FUNC>
void cxx::Bits::Bst< Node, Get_key, Compare >::remove_tree (
    Bst_node * head,
    FUNC && callback) [inline], [static], [protected]
  
```

Remove all elements in the subtree of head.

#### Parameters


<i>head</i>	Head of the the subtree to remove
<i>callback</i>	Optional function called on each removed element.

Definition at line 152 of file [bst.h](#).

References [head\(\)](#), [cxx::Bits::Direction::L](#), [cxx::Bits::Bst\\_node::next\(\)](#), [cxx::Bits::Direction::R](#), and [remove\\_tree\(\)](#).

Referenced by [remove\\_all\(\)](#), and [remove\\_tree\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



#### 15.25.2.14 `rend()` [1/2]

```
template<typename Node, typename Get_key, typename Compare>
Rev_iterator cxx::Bits::Bst< Node, Get_key, Compare >::rend () [inline]
```

Get the end marker for the mutable backward iterator.

##### Returns

The end marker for mutable backward iterator.

Definition at line 211 of file [bst.h](#).

#### 15.25.2.15 `rend()` [2/2]

```
template<typename Node, typename Get_key, typename Compare>
Const_rev_iterator cxx::Bits::Bst< Node, Get_key, Compare >::rend () const [inline]
```

Get the end marker for the constant backward iterator.

##### Returns

The end marker for the constant backward iterator.

Definition at line 200 of file [bst.h](#).

The documentation for this class was generated from the following file:


- [l4/cxx/bits/bst.h](#)

## 15.26 cxx::Bits::Bst\_node Class Reference

Basic type of a node in a binary search tree (BST).

```
#include <bst_base.h>
```

Inheritance diagram for cxx::Bits::Bst\_node:





Collaboration diagram for cxx::Bits::Bst\_node:

cxx::Bits::Bst_node	
#	Bst_node()
#	Bst_node()
#	next()
#	next()
#	next_p()
#	next()
#	rotate()
*	next()
*	next()
*	next_p()
*	next()
*	rotate()

### Protected Member Functions

- **Bst\_node** ()  
*Create uninitialized node.*
- **Bst\_node** (bool)  
*Create initialized node.*

### Static Protected Member Functions

#### Access to BST linkage.

Provide access to the tree linkage to inherited classes. Inherited nodes, such as AVL nodes should make these methods private via 'using'

- static **Bst\_node** \* **next** (**Bst\_node** const \*p, **Direction** d)  
*Get next node in direction d.*
- static void **next** (**Bst\_node** \*p, **Direction** d, **Bst\_node** \*n)  
*Set next node of p in direction d to n.*
- static **Bst\_node** \*\* **next\_p** (**Bst\_node** \*p, **Direction** d)  
*Get pointer to link in direction d.*
- template<typename Node>  
static Node \* **next** (**Bst\_node** const \*p, **Direction** d)  
*Get next node in direction d as type Node.*
- static void **rotate** (**Bst\_node** \*\*t, **Direction** idir)  
*Rotate subtree t in the opposite direction of idir.*

### 15.26.1 Detailed Description

Basic type of a node in a binary search tree (BST).

Definition at line 70 of file [bst\\_base.h](#).

The documentation for this class was generated from the following file:

- [l4/cxx/bits/bst\\_base.h](#)

## 15.27 cxx::Bits::Direction Struct Reference

The direction to go in a binary search tree.

```
#include <bst_base.h>
```

Collaboration diagram for cxx::Bits::Direction:

cxx::Bits::Direction
<ul style="list-style-type: none"> <li>+ Direction()</li> <li>+ Direction()</li> <li>+ Direction()</li> <li>+ operator!()</li> <li>+ operator==()</li> <li>+ operator!=()</li> <li>+ operator==()</li> <li>+ operator!=()</li> <li>* operator==()</li> <li>* operator!=()</li> <li>* operator==()</li> <li>* operator!=()</li> </ul>

### Public Types

- enum [Direction\\_e](#) { [L](#) = 0 , [R](#) = 1 , [N](#) = 2 }

*The literal direction values.*

## Public Member Functions

- **Direction** ()=default  
*Uninitialized direction.*
- **Direction** ([Direction\\_e](#) d)  
*Convert a literal direction ([L](#), [R](#), [N](#)) to an object.*
- **Direction** (bool b)  
*Convert a boolean to a direction (false == [L](#), true == [R](#)).*
- **Direction operator!** () const  
*Negate the direction.*

## Comparison operators (equality and inequality)

- bool **operator==** ([Direction\\_e](#) o) const  
*Compare for equality.*
- bool **operator!=** ([Direction\\_e](#) o) const  
*Compare for inequality.*
- bool **operator==** ([Direction](#) o) const  
*Compare for equality.*
- bool **operator!=** ([Direction](#) o) const  
*Compare for inequality.*

## 15.27.1 Detailed Description

The direction to go in a binary search tree.

Definition at line 28 of file [bst\\_base.h](#).

## 15.27.2 Member Enumeration Documentation

### 15.27.2.1 Direction\_e

```
enum cxx::Bits::Direction::Direction_e
```

The literal direction values.

#### Enumerator

L	Go to the left child.
R	Go to the right child.
N	Stop.

Definition at line 31 of file [bst\\_base.h](#).

### 15.27.3 Member Function Documentation

#### 15.27.3.1 operator"!")()

```
Direction cxx::Bits::Direction::operator! () const [inline]
```

Negate the direction.


##### Note

This is only defined for a current value of [L](#) or [R](#)

Definition at line [52](#) of file [bst\\_base.h](#).

References [Direction\(\)](#).

Here is the call graph for this function:



The documentation for this struct was generated from the following file:


- [I4/cxx/bits/bst\\_base.h](#)

## 15.28 cxx::Bits::Smart\_ptr\_list< ITEM > Class Template Reference


[List](#) of smart-pointer-managed objects.

```
#include <smart_ptr_list.h>
```

Inheritance diagram for cxx::Bits::Smart\_ptr\_list< ITEM >:



Collaboration diagram for `cxx::Bits::Smart_ptr_list< ITEM >`:



### Public Member Functions

- void **push\_front** (Next\_type &&e)  
*Add an element to the front of the list.*
- void **push\_front** (Next\_type const &e)  
*Add an element to the front of the list.*
- void **push\_back** (Next\_type &&e)  
*Add an element at the end of the list.*
- void **push\_back** (Next\_type const &e)  
*Add an element at the end of the list.*
- Value\_type \* **front** () const  
*Return a pointer to the first element in the list.*
- Next\_type **pop\_front** ()  
*Remove the element in front of the list and return it.*
- bool **empty** () const  
*Check if the list is empty.*

### 15.28.1 Detailed Description

```
template<typename ITEM>
class cxx::Bits::Smart_ptr_list< ITEM >
```

[List](#) of smart-pointer-managed objects.

### Template Parameters

---

<i>ITEM</i>	Type of the list items.
-------------	-------------------------

The list is implemented as a single-linked list connected via smart pointers, so that they are automatically cleaned up when they are removed from the list.

Definition at line 46 of file [smart\\_ptr\\_list.h](#).

## 15.28.2 Member Function Documentation

### 15.28.2.1 `pop_front()`

```
template<typename ITEM>
Next_type cxx::Bits::Smart_ptr_list< ITEM >::pop_front () [inline]
```

Remove the element in front of the list and return it.

#### Returns

The element that was previously in front of the list as a managed pointer or a nullptr-equivalent when the list was already empty.

Definition at line 149 of file [smart\\_ptr\\_list.h](#).

The documentation for this class was generated from the following file:


- [I4/cxx/bits/smart\\_ptr\\_list.h](#)

## 15.29 `cxx::Bits::Smart_ptr_list_item< T, STORE_T >` Class Template Reference

[List](#) item for an arbitrary item in a [Smart\\_ptr\\_list](#).

```
#include <smart_ptr_list.h>
```

Inheritance diagram for `cxx::Bits::Smart_ptr_list_item< T, STORE_T >`:



Collaboration diagram for `cxx::Bits::Smart_ptr_list_item< T, STORE_T >`:



### 15.29.1 Detailed Description

```

template<typename T, typename STORE_T>
class cxx::Bits::Smart_ptr_list_item< T, STORE_T >

```

[List](#) item for an arbitrary item in a [Smart\\_ptr\\_list](#).



## Template Parameters

<i>T</i>	Type of object to be stored in the list.
<i>STORE↔ _T</i>	Storage type for pointer to next item. The class must implement a <code>get()</code> function that returns a pointer to the stored object and destroy the stored object when the item goes out of scope.

Definition at line 27 of file [smart\\_ptr\\_list.h](#).

The documentation for this class was generated from the following file:


- [I4/cxx/bits/smart\\_ptr\\_list.h](#)

## 15.30 `cxx::Elide_dtor< T >` Class Template Reference

Wrapper class to remove destructor calls.

```
#include <elide_dtor>
```

Collaboration diagram for `cxx::Elide_dtor< T >`:



### 15.30.1 Detailed Description

```
template<typename T>
class cxx::Elide_dtor< T >
```

Wrapper class to remove destructor calls.

Use this class for global or static local objects that shall not be destructed. This can save some code size if the destructor of `T` is not trivial. It also prevents calls to `atexit()` at runtime.

#### Attention

Be careful if you use [Elide\\_dtor](#) in the global scope. Even if `T` is trivially constructible, the wrapper will force the compiler to emit a static initializer!

Definition at line 28 of file [elide\\_dtor](#).

The documentation for this class was generated from the following file:


- [I4/cxx/elide\\_dtor](#)

## 15.31 cxx::H\_list< T, POLICY > Class Template Reference


General double-linked list of unspecified [cxx::H\\_list\\_item](#) elements.

```
#include <hlist>
```

Inheritance diagram for `cxx::H_list< T, POLICY >`:



Collaboration diagram for `cxx::H_list< T, POLICY >`:



### Public Member Functions

- void **add** (T \*e)  
*Add element to the front of the list.*
- void **push\_front** (T \*e)  
*Add element to the front of the list.*
- T \* **pop\_front** ()  
*Remove and return the head element of the list.*
- Iterator **insert** (T \*e, Iterator const &pred)  
*Insert an element at the iterator position.*

## Public Member Functions inherited from `cxx::Bits::Basic_list< POLICY >`

- `bool empty () const`  
*Check if the list is empty.*
- `Value_type front () const`  
*Return the first element in the list.*
- `void clear ()`  
*Remove all elements from the list.*
- `Iterator begin ()`  
*Return an iterator to the beginning of the list.*
- `Const_iterator begin () const`  
*Return a const iterator to the beginning of the list.*
- `Const_iterator end () const`  
*Return a const iterator to the end of the list.*
- `Iterator end ()`  
*Return an iterator to the end of the list.*

## Static Public Member Functions

- `static Iterator iter (T *c)`  
*Return an iterator for an arbitrary list element.*
- `static bool in_list (T const *e)`  
*Check if the given element is currently part of a list.*
- `static Iterator insert_after (T *e, Iterator const &pred)`  
*Insert an element after the iterator position.*
- `static void insert_before (T *e, Iterator const &succ)`  
*Insert an element before the iterator position.*
- `static void replace (T *p, T *e)`  
*Replace an element in a list with a new element.*
- `static void remove (T *e)`  
*Remove the given element from its list.*
- `static Iterator erase (Iterator const &e)`  
*Remove the element at the given iterator position.*

## Static Public Member Functions inherited from `cxx::Bits::Basic_list< POLICY >`

- `static Const_iterator iter (Const_value_type c)`  
*Return a const iterator that begins at the given element.*

## Additional Inherited Members

## Protected Attributes inherited from `cxx::Bits::Basic_list< POLICY >`

- `POLICY::Head_type _f`  
*Pointer to front of the list.*

### 15.31.1 Detailed Description

```
template<typename T, typename POLICY = Bits::Basic_list_policy< T, H_list_item>>
class cxx::H_list< T, POLICY >
```

General double-linked list of unspecified `cxx::H_list_item` elements.

Most of the time, you want to use `H_list_t`.

Definition at line 69 of file `hlist`.

### 15.31.2 Member Function Documentation

#### 15.31.2.1 `erase()`

```
template<typename T, typename POLICY = Bits::Basic_list_policy< T, H_list_item>>
Iterator cxx::H_list< T, POLICY >::erase (
    Iterator const & e) [inline], [static]
```

Remove the element at the given iterator position.

##### Parameters

<code>e</code>	Iterator pointing to the element to be removed. Must not point to <code>end()</code> .
----------------	--

##### Returns

New iterator pointing to the element after the removed one.

##### Note

The `hlist` implementation guarantees that the original iterator is still valid after the element has been removed. In fact, the iterator returned is the same as the one supplied in the `e` parameter.

Definition at line 236 of file `hlist`.

#### 15.31.2.2 `insert()`

```
template<typename T, typename POLICY = Bits::Basic_list_policy< T, H_list_item>>
Iterator cxx::H_list< T, POLICY >::insert (
    T * e,
    Iterator const & pred) [inline]
```

Insert an element at the iterator position.

##### Parameters

<i>e</i>	New Element to be inserted
<i>pred</i>	Iterator pointing to the element after which the element will be inserted. If <a href="#">end()</a> is given, the element will be inserted at the beginning of the queue.

**Returns**

Iterator pointing to the newly inserted element.

Definition at line [133](#) of file [hlist](#).

**15.31.2.3 insert\_after()**

```
template<typename T, typename POLICY = Bits::Basic_list_policy< T, H_list_item>>
Iterator cxx::H\_list< T, POLICY >::insert_after (
    T * e,
    Iterator const & pred) [inline], [static]
```

Insert an element after the iterator position.

**Parameters**

<i>e</i>	New element to be inserted.
<i>pred</i>	Iterator pointing to the element after which the element will be inserted. Must not be <a href="#">end()</a> .

**Returns**

Iterator pointing to the newly inserted element.

**Precondition**

The list must not be empty.

Definition at line [160](#) of file [hlist](#).

**15.31.2.4 insert\_before()**

```
template<typename T, typename POLICY = Bits::Basic_list_policy< T, H_list_item>>
void cxx::H\_list< T, POLICY >::insert_before (
    T * e,
    Iterator const & succ) [inline], [static]
```

Insert an element before the iterator position.

**Parameters**

<i>e</i>	New element to be inserted.
<i>succ</i>	Iterator pointing to the element before which the element will be inserted. Must not be <code>end()</code> .

Definition at line 180 of file `hlist`.

#### 15.31.2.5 `iter()`

```
template<typename T, typename POLICY = Bits::Basic_list_policy< T, H_list_item>>
Iterator cxx::H_list< T, POLICY >::iter (
    T * c)    [inline], [static]
```

Return an iterator for an arbitrary list element.

##### Parameters

<i>c</i>	<code>List</code> element to start the iteration.
----------	---

##### Returns

A mutable forward iterator.


##### Precondition

The element must be in a list.

Definition at line 93 of file `hlist`.

Referenced by `cxx::H_list< Timeout >::insert()`, and `cxx::H_list< Timeout >::insert_after()`.

Here is the caller graph for this function:



### 15.31.2.6 pop\_front()

```
template<typename T, typename POLICY = Bits::Basic_list_policy< T, H_list_item>>
T * cxx::H_list< T, POLICY >::pop_front () [inline]
```

Remove and return the head element of the list.

#### Precondition

The list must not be empty or the behaviour will be undefined.

Definition at line 116 of file [hlist](#).

### 15.31.2.7 remove()

```
template<typename T, typename POLICY = Bits::Basic_list_policy< T, H_list_item>>
void cxx::H_list< T, POLICY >::remove (
    T * e) [inline], [static]
```

Remove the given element from its list.


#### Parameters

<i>e</i>	Element to be removed. Must be in a list.
----------	---

Definition at line 220 of file [hlist](#).

Referenced by [cxx::H\\_list< Timeout >::pop\\_front\(\)](#).

Here is the caller graph for this function:





**15.31.2.8 replace()**

```
template<typename T, typename POLICY = Bits::Basic_list_policy< T, H_list_item>>
void cxx::H_list< T, POLICY >::replace (
    T * p,
    T * e) [inline], [static]
```

Replace an element in a list with a new element.

**Parameters**

<i>p</i>	Element in list to be replaced.
<i>e</i>	Replacement element, must not yet be in a list.

**Precondition**

*p* and *e* must not be NULL.

After the operation the *p* element is no longer in the list and may be reused.

Definition at line 204 of file [hlist](#).

The documentation for this class was generated from the following file:


- I4/cxx/hlist

**15.32 cxx::H\_list\_item\_t< ELEM\_TYPE > Class Template Reference**


Basic element type for a double-linked [H\\_list](#).

```
#include <hlist>
```

Inheritance diagram for `cxx::H_list_item_t< ELEM_TYPE >`:



Collaboration diagram for cxx::H\_list\_item\_t< ELEM\_TYPE >:



### Public Member Functions

- [H\\_list\\_item\\_t\(\)](#)  
*Constructor.*
- [~H\\_list\\_item\\_t\(\)](#) noexcept  
*Destructor.*

### 15.32.1 Detailed Description

```
template<typename ELEM_TYPE>
class cxx::H_list_item_t< ELEM_TYPE >
```

Basic element type for a double-linked [H\\_list](#).

#### Template Parameters

<i>ELEM_TYPE</i>	Base class of the list element.
------------------	---------------------------------

Definition at line 22 of file [hlist](#).

### 15.32.2 Constructor & Destructor Documentation

#### 15.32.2.1 H\_list\_item\_t()

```
template<typename ELEM_TYPE>
cxx::H_list_item_t< ELEM_TYPE >::H_list_item_t () [inline]
```

Constructor.

Creates an element that is not in any list.

Definition at line 30 of file [hlist](#).

### 15.32.2.2 ~H\_list\_item\_t()

```
template<typename ELEM_TYPE>
cxx::H_list_item_t< ELEM_TYPE >::~~H_list_item_t () [inline], [noexcept]
```

Destructor.

Automatically removes the element from any list it still might be enchainned in.

Definition at line 37 of file [hlist](#).

The documentation for this class was generated from the following file:


- I4/cxx/hlist

## 15.33 cxx::H\_list\_t< T > Struct Template Reference


Double-linked list of typed [H\\_list\\_item\\_t](#) elements.

```
#include <hlist>
```

Inheritance diagram for cxx::H\_list\_t< T >:



Collaboration diagram for `cxx::H_list_t< T >`:



### Additional Inherited Members

### Public Member Functions inherited from

**`cxx::H_list< T, Bits::Basic_list_policy< T, H_list_item_t< T > > >`**

- `void add (T *e)`

- *Add element to the front of the list.*
- void **push\_front** (T \*e)  
*Add element to the front of the list.*
- T \* **pop\_front** ()  
*Remove and return the head element of the list.*
- Iterator **insert** (T \*e, Iterator const &pred)  
*Insert an element at the iterator position.*

### Public Member Functions inherited from

`cxx::Bits::Basic_list< Bits::Basic_list_policy< T, H_list_item_t< T > > >`

- bool **empty** () const  
*Check if the list is empty.*
- Value\_type **front** () const  
*Return the first element in the list.*
- void **clear** ()  
*Remove all elements from the list.*
- Iterator **begin** ()  
*Return an iterator to the beginning of the list.*
- Const\_iterator **end** () const  
*Return a const iterator to the end of the list.*

### Static Public Member Functions inherited from

`cxx::H_list< T, Bits::Basic_list_policy< T, H_list_item_t< T > > >`

- static Iterator **iter** (T \*c)  
*Return an iterator for an arbitrary list element.*
- static bool **in\_list** (T const \*e)  
*Check if the given element is currently part of a list.*
- static Iterator **insert\_after** (T \*e, Iterator const &pred)  
*Insert an element after the iterator position.*
- static void **insert\_before** (T \*e, Iterator const &succ)  
*Insert an element before the iterator position.*
- static void **replace** (T \*p, T \*e)  
*Replace an element in a list with a new element.*
- static void **remove** (T \*e)  
*Remove the given element from its list.*
- static Iterator **erase** (Iterator const &e)  
*Remove the element at the given iterator position.*

### Static Public Member Functions inherited from

`cxx::Bits::Basic_list< Bits::Basic_list_policy< T, H_list_item_t< T > > >`

- static Const\_iterator **iter** (Const\_value\_type c)  
*Return a const iterator that begins at the given element.*

**Protected Attributes inherited from****cxx::Bits::Basic\_list< Bits::Basic\_list\_policy< T, H\_list\_item\_t< T > > >**

- Bits::Basic\_list\_policy< T, H\_list\_item\_t< T > >::Head\_type \_f

*Pointer to front of the list.***15.33.1 Detailed Description**

```
template<typename T>
struct cxx::H_list_t< T >
```

Double-linked list of typed [H\\_list\\_item\\_t](#) elements.

**Note**

H\_lists are not self-cleaning. Elements that are still chained during destruction are not removed and will therefore be in an undefined state after the destruction.

Definition at line [248](#) of file [hlist](#).

The documentation for this struct was generated from the following file:

- I4/cxx/hlist

**15.34 cxx::List< D, Alloc > Class Template Reference**

Doubly linked list, with internal allocation.

```
#include <list>
```

Collaboration diagram for cxx::List< D, Alloc >:

cxx::List< D, Alloc >	
+	push_back()
+	push_front()
+	remove()
+	size()
+	operator[]()
+	operator[]()
+	items()



## Data Structures

- class `Iter`  
*Iterator.*

## Public Member Functions

- void **push\_back** (D const &d) noexcept  
*Add element at the end of the list.*
- void **push\_front** (D const &d) noexcept  
*Add element at the beginning of the list.*
- void **remove** (Iter const &i) noexcept  
*Remove element pointed to by the iterator.*
- unsigned long **size** () const noexcept  
*Get the length of the list.*
- D const & **operator[]** (unsigned long idx) const noexcept  
*Random access.*
- D & **operator[]** (unsigned long idx) noexcept  
*Random access.*
- `Iter` **items** () noexcept  
*Get iterator for the list elements.*

### 15.34.1 Detailed Description

`template<typename D, template< typename A > class Alloc = New_allocator>`  
`class cxx::List< D, Alloc >`

Doubly linked list, with internal allocation.

Container for items of type D, implemented by a doubly linked list. Alloc defines the allocator policy.

Definition at line 323 of file `list`.

### 15.34.2 Member Function Documentation

#### 15.34.2.1 `operator[]()` [1/2]

```
template<typename D, template< typename A > class Alloc = New_allocator>
D const & cxx::List< D, Alloc >::operator[] (
    unsigned long idx) const [inline], [noexcept]
```

Random access.

Complexity is O(n).

Definition at line 393 of file `list`.

### 15.34.2.2 operator[]() [2/2]

```
template<typename D, template< typename A > class Alloc = New_allocator>
D & cxx::List< D, Alloc >::operator[] (
    unsigned long idx) [inline], [noexcept]
```

Random access.

Complexity is O(n).

Definition at line 397 of file [list](#).

The documentation for this class was generated from the following file:


- l4/cxx/list

## 15.35 cxx::List< D, Alloc >::Iter Class Reference

Iterator.

```
#include <list>
```

Collaboration diagram for cxx::List< D, Alloc >::Iter:



### Public Member Functions

- **operator E\* ()** const noexcept  
*operator for testing validity (syntactically equal to pointers)*

### 15.35.1 Detailed Description

```
template<typename D, template< typename A > class Alloc = New_allocator>
class cxx::List< D, Alloc >::Iter
```

Iterator.

Forward and backward iterable.

Definition at line 343 of file [list](#).

The documentation for this class was generated from the following file:


- l4/cxx/list

## 15.36 `cxx::List_alloc` Class Reference

Standard list-based allocator.

```
#include <list_alloc>
```

Collaboration diagram for `cxx::List_alloc`:



### Public Member Functions

- [List\\_alloc](#) ()  
*Initializes an empty list allocator.*
- void [free](#) (void \*block, unsigned long size, bool initial\_free=false)  
*Return a free memory block to the allocator.*
- void \* [alloc](#) (unsigned long size, unsigned long align, unsigned long lower=0, unsigned long upper=~0UL)  
*Allocate a memory block.*
- void \* [alloc\\_max](#) (unsigned long min, unsigned long \*max, unsigned long align, unsigned granularity, unsigned long lower=0, unsigned long upper=~0UL)  
*Allocate a memory block of  $min \leq size \leq max$ .*
- unsigned long [avail](#) ()  
*Get the amount of available memory.*

### 15.36.1 Detailed Description

Standard list-based allocator.

Definition at line 22 of file [list\\_alloc](#).

## 15.36.2 Constructor & Destructor Documentation

### 15.36.2.1 List\_alloc()

```
cxx::List_alloc::List_alloc () [inline]
```

Initializes an empty list allocator.

#### Note

To initialize the allocator with available memory use the [free\(\)](#) function.

Definition at line 47 of file [list\\_alloc](#).

## 15.36.3 Member Function Documentation

### 15.36.3.1 alloc()

```
void * cxx::List_alloc::alloc (
    unsigned long size,
    unsigned long align,
    unsigned long lower = 0,
    unsigned long upper = ~0UL) [inline]
```

Allocate a memory block.

#### Parameters

<i>size</i>	Size of the memory block.
<i>align</i>	Alignment constraint.
<i>lower</i>	Lower bound of the physical region the memory block should be allocated from.
<i>upper</i>	Upper bound of the physical region the memory block should be allocated from, value is inclusive.

#### Returns

Pointer to memory block

#### Precondition

```
0 < size <= ~0UL - 32.
```

Definition at line 390 of file [list\\_alloc](#).

## 15.36.3.2 alloc\_max()

```
void * cxx::List_alloc::alloc_max (
    unsigned long min,
    unsigned long * max,
    unsigned long align,
    unsigned granularity,
    unsigned long lower = 0,
    unsigned long upper = ~0UL) [inline]
```

Allocate a memory block of  $\text{min} \leq \text{size} \leq \text{max}$ .

## Parameters

	<i>min</i>	Minimal size to allocate (in bytes).
<i>in, out</i>	<i>max</i>	Maximum size to allocate (in bytes). The actual allocated size is returned here.
	<i>align</i>	Alignment constraint.
	<i>granularity</i>	Granularity to use for the allocation (power of 2).
	<i>lower</i>	Lower bound of the physical region the memory block should be allocated from.
	<i>upper</i>	Upper bound of the physical region the memory block should be allocated from, value is inclusive.

## Returns

Pointer to memory block

## Precondition


$0 < \text{min} \leq \sim 0\text{UL} - 32$ .

$0 < \text{max}$ .

Definition at line 270 of file [list\\_alloc](#).

References [l4\\_round\\_size\(\)](#), and [l4\\_trunc\\_size\(\)](#).

Here is the call graph for this function:



### 15.36.3.3 avail()

```
unsigned long cxx::List_alloc::avail () [inline]
```

Get the amount of available memory.

#### Returns

Available memory in bytes

Definition at line 478 of file [list\\_alloc](#).

### 15.36.3.4 free()

```
void cxx::List_alloc::free (
    void * block,
    unsigned long size,
    bool initial_free = false) [inline]
```

Return a free memory block to the allocator.

#### Parameters

<i>block</i>	Pointer to memory block.
<i>size</i>	Size of memory block.
<i>initial_free</i>	Set to true for putting fresh memory to the allocator. This will enforce alignment on that memory.

#### Precondition

*block* must not be NULL.  
 $2 * \text{sizeof}(\text{void} *) \leq \text{size} \leq \sim 0\text{UL} - 32$ .

Definition at line 229 of file [list\\_alloc](#).

The documentation for this class was generated from the following file:

- I4/cxx/list\_alloc

## 15.37 cxx::List\_item Class Reference

Basic list item.

```
#include <list>
```

Collaboration diagram for cxx::List\_item:

cxx::List_item
<ul style="list-style-type: none"> <li>+ get_prev_item()</li> <li>+ get_next_item()</li> <li>+ insert_prev_item()</li> <li>+ insert_next_item()</li> <li>+ remove_me()</li> <li>+ push_back()</li> <li>+ push_front()</li> <li>+ remove()</li> </ul>

### Data Structures

- class [Iter](#)  
*Iterator for a list of ListItem-s.*
- class [T\\_iter](#)  
*Iterator for derived classes from ListItem.*

### Public Member Functions

- List\_item \* **get\_prev\_item** () const noexcept  
*Get previous item.*
- List\_item \* **get\_next\_item** () const noexcept  
*Get next item.*
- void **insert\_prev\_item** (List\_item \*p) noexcept  
*Insert item p before this item.*
- void **insert\_next\_item** (List\_item \*p) noexcept  
*Insert item p after this item.*
- void **remove\_me** () noexcept  
*Remove this item from the list.*

## Static Public Member Functions

- `template<typename C, typename N>`  
`static C * push\_back (C *head, N *p) noexcept`  
*Append item to a list.*
- `template<typename C, typename N>`  
`static C * push\_front (C *head, N *p) noexcept`  
*Prepend item to a list.*
- `template<typename C, typename N>`  
`static C * remove (C *head, N *p) noexcept`  
*Remove item from a list.*

### 15.37.1 Detailed Description

Basic list item.

Basic item that can be member of a doubly linked, cyclic list.

Definition at line [26](#) of file [list](#).

### 15.37.2 Member Function Documentation

#### 15.37.2.1 [push\\_back\(\)](#)

```
template<typename C, typename N>
C * cxx::List_item::push_back (
    C * head,
    N * p) [inline], [static], [noexcept]
```

Append item to a list.

Convenience function for empty-head corner case.

#### Parameters

<i>head</i>	Pointer to the current list head.
<i>p</i>	Pointer to new item.

#### Returns

the pointer to the new head.

Definition at line [237](#) of file [list](#).

Referenced by [cxx::List< D, Alloc >::push\\_back\(\)](#).

Here is the caller graph for this function:





### 15.37.2.2 push\_front()

```
template<typename C, typename N>
C * cxx::List_item::push_front (
    C * head,
    N * p) [inline], [static], [noexcept]
```

Prepend item to a list.

Convenience function for empty-head corner case.

#### Parameters

<i>head</i>	pointer to the current list head.
<i>p</i>	pointer to new item.


#### Returns

the pointer to the new head.

Definition at line 248 of file [list](#).

Referenced by [cxx::List< D, Alloc >::push\\_front\(\)](#).

Here is the caller graph for this function:



### 15.37.2.3 remove()

```
template<typename C, typename N>
C * cxx::List_item::remove (
    C * head,
    N * p) [inline], [static], [noexcept]
```

Remove item from a list.

Convenience function for remove-head corner case.

#### Parameters

<i>head</i>	pointer to the current list head.
<i>p</i>	pointer to the item to remove.

#### Returns

the pointer to the new head.

Definition at line 258 of file [list](#).

Referenced by [cxx::List< D, Alloc >::remove\(\)](#).

Here is the caller graph for this function:



The documentation for this class was generated from the following file:


- `I4/cxx/list`

## 15.38 cxx::List\_item::Iter Class Reference


Iterator for a list of ListItem-s.

```
#include <list>
```

Inheritance diagram for cxx::List\_item::Iter:



Collaboration diagram for cxx::List\_item::Iter:



## Public Member Functions

- List\_item \* **remove\_me** () noexcept  
*Remove item pointed to by iterator, and return pointer to element.*

### 15.38.1 Detailed Description

Iterator for a list of ListItem-s.

The Iterator iterates till it finds the first element again.

Definition at line 34 of file [list](#).

The documentation for this class was generated from the following file:


- l4/cxx/list

## 15.39 cxx::List\_item::T\_iter< T, Poly > Class Template Reference


Iterator for derived classes from ListItem.

```
#include <list>
```

Inheritance diagram for cxx::List\_item::T\_iter< T, Poly >:



Collaboration diagram for cxx::List\_item::T\_iter< T, Poly >:



#### Additional Inherited Members

#### Public Member Functions inherited from `cxx::List_item::Iter`

- `List_item * remove_me () noexcept`  
*Remove item pointed to by iterator, and return pointer to element.*

### 15.39.1 Detailed Description

```
template<typename T, bool Poly = false>
class cxx::List_item::T_iter< T, Poly >
```

Iterator for derived classes from ListItem.

Allows direct access to derived classes by \* operator.

Example: `class Foo : public ListItem { public: typedef T_iter<Foo> Iter; ... };`

Definition at line 108 of file [list](#).

The documentation for this class was generated from the following file:


- `I4/cxx/list`

## 15.40 `cxx::Lt_functor< Obj >` Struct Template Reference

Generic comparator class that defaults to the less-than operator.

```
#include <std_ops>
```

Collaboration diagram for `cxx::Lt_functor< Obj >`:



### 15.40.1 Detailed Description

```
template<typename Obj>
struct cxx::Lt_functor< Obj >
```

Generic comparator class that defaults to the less-than operator.

Definition at line 18 of file [std\\_ops](#).

The documentation for this struct was generated from the following file:


- `I4/cxx/std_ops`

## 15.41 `cxx::New_allocator< _Type >` Class Template Reference


Standard allocator based on `operator new ()` .

```
#include <std_alloc>
```

Inheritance diagram for `cxx::New_allocator<_Type>`:



Collaboration diagram for `cxx::New_allocator<_Type>`:



### 15.41.1 Detailed Description

```

template<typename _Type>
class cxx::New_allocator<_Type>

```

Standard allocator based on `operator new ()`.

This allocator is the default allocator used for the *cxx Containers*, such as `cxx::Avl_set` and `cxx::Avl_map`, to allocate the internal data structures.

Definition at line 56 of file `std_alloc`.

The documentation for this class was generated from the following file:


- `I4/cxx/std_alloc`

## 15.42 cxx::Nothrow Class Reference

Helper type to distinguish the `operator new` version that does not throw exceptions.

```
#include <std_alloc>
```

Collaboration diagram for `cxx::Nothrow`:



### 15.42.1 Detailed Description

Helper type to distinguish the `operator new` version that does not throw exceptions.

Definition at line 19 of file [std\\_alloc](#).

The documentation for this class was generated from the following file:

- `I4/cxx/std_alloc`


## 15.43 cxx::Pair< First, Second > Struct Template Reference

[Pair](#) of two values.


```
#include <pair>
```



Inheritance diagram for cxx::Pair< First, Second >:



Collaboration diagram for cxx::Pair< First, Second >:



## Public Types

- typedef First **First\_type**

*Type of first value.*

- typedef Second **Second\_type**

*Type of second value.*

## Public Member Functions

- template<typename A1, typename A2>  
[Pair](#) (A1 &&[first](#), A2 &&[second](#))  
*Create a pair from the two values.*
- template<typename A1>  
[Pair](#) (A1 &&[first](#))  
*Create a pair, default constructing the second value.*
- **Pair** ()=default  
*Default construction.*

## Data Fields

- First **first**  
*First value.*
- Second **second**  
*Second value.*

## 15.43.1 Detailed Description

```
template<typename First, typename Second>
struct cxx::Pair< First, Second >
```

[Pair](#) of two values.

Standard container for a pair of values.

### Parameters

<i>First</i>	Type of the first value.
<i>Second</i>	Type of the second value.

Definition at line 27 of file [pair](#).

## 15.43.2 Constructor & Destructor Documentation

### 15.43.2.1 Pair() [1/2]

```
template<typename First, typename Second>
template<typename A1, typename A2>
cxx::Pair< First, Second >::Pair (
    A1 && first,
    A2 && second) [inline]
```

Create a pair from the two values.

#### Parameters

<i>first</i>	The first value.
<i>second</i>	The second value.

Definition at line 45 of file [pair](#).

### 15.43.2.2 Pair() [2/2]

```
template<typename First, typename Second>
template<typename A1>
cxx::Pair< First, Second >::Pair (
    A1 && first) [inline]
```

Create a pair, default constructing the second value.

#### Parameters

<i>first</i>	The first value.
--------------	------------------

Definition at line 53 of file [pair](#).

The documentation for this struct was generated from the following file:


- [l4/cxx/pair](#)

## 15.44 cxx::Pair\_first\_compare< Cmp, Typ > Class Template Reference

Comparison functor for [Pair](#).

```
#include <pair>
```

Collaboration diagram for `cxx::Pair_first_compare< Cmp, Typ >`:



### Public Member Functions

- `Pair_first_compare` (`Cmp const &cmp=Cmp()`)  
*Construction.*
- `bool operator()` (`Typ const &l, Typ const &r`) `const`  
*Do the comparison based on the first value.*

## 15.44.1 Detailed Description

```
template<typename Cmp, typename Typ>
class cxx::Pair_first_compare< Cmp, Typ >
```

Comparison functor for [Pair](#).

### Parameters

<i>Cmp</i>	Comparison functor for the first value of the pair.
<i>Typ</i>	The pair type.

This functor can be used to compare [Pair](#) values with respect to the first value.

Definition at line 74 of file [pair](#).

## 15.44.2 Constructor & Destructor Documentation

### 15.44.2.1 Pair\_first\_compare()

```
template<typename Cmp, typename Typ>
cxx::Pair_first_compare< Cmp, Typ >::Pair_first_compare (
    Cmp const & cmp = Cmp()) [inline]
```

Construction.

**Parameters**

<code>cmp</code>	The comparison functor used for the first value.
------------------	--

Definition at line 84 of file [pair](#).

**15.44.3 Member Function Documentation****15.44.3.1 `operator>()()`**

```
template<typename Cmp, typename Typ>
bool cxx::Pair_first_compare< Cmp, Typ >::operator() (
    Typ const & l,
    Typ const & r) const [inline]
```

Do the comparison based on the first value.

**Parameters**

<code>l</code>	The lefthand value.
<code>r</code>	The righthand value.

Definition at line 91 of file [pair](#).

The documentation for this class was generated from the following file:


- [l4/cxx/pair](#)

**15.45 `cxx::Ref_obj_list_item< T >` Struct Template Reference**


Item for list linked via [cxx::Ref\\_ptr](#) with default reference counting.

```
#include <ref_ptr_list>
```

Inheritance diagram for `cxx::Ref_obj_list_item< T >`:



Collaboration diagram for `cxx::Ref_obj_list_item< T >`:



### 15.45.1 Detailed Description

```
template<typename T>
struct cxx::Ref_obj_list_item< T >
```

Item for list linked via `cxx::Ref_ptr` with default reference counting.

Definition at line 26 of file `ref_ptr_list`.

The documentation for this struct was generated from the following file:


- `I4/cxx/ref_ptr_list`

## 15.46 `cxx::Ref_ptr< T, CNT >` Class Template Reference

A reference-counting pointer with automatic cleanup.

```
#include <ref_ptr>
```

Inheritance diagram for `cxx::Ref_ptr< T, CNT >`:





Collaboration diagram for `cxx::Ref_ptr< T, CNT >`:

<code>cxx::Ref_ptr&lt; T, CNT &gt;</code>	
+	<code>Ref_ptr()</code>
+	<code>Ref_ptr()</code>
+	<code>Ref_ptr()</code>
+	<code>Ref_ptr()</code>
+	<code>Ref_ptr()</code>
+	<code>get()</code>
+	<code>ptr()</code>
+	<code>release()</code>

### Public Member Functions

- **`Ref_ptr()`** noexcept  
*Default constructor creates a pointer with no managed object.*
- **`Ref_ptr`** (`Wp const &o`) noexcept  
*Create a shared pointer from a weak pointer.*
- **`Ref_ptr`** (`decltype(nullptr) n`) noexcept  
*allow creation from `nullptr`*
- `template<typename X>`  
**`Ref_ptr`** (`X *o`) noexcept  
*Create a shared pointer from a raw pointer.*
- **`Ref_ptr`** (`T *o, bool d`) noexcept  
*Create a shared pointer from a raw pointer without creating a new reference.*
- `T * get ()` const noexcept  
*Return a raw pointer to the object this shared pointer points to.*
- `T * ptr ()` const noexcept  
*Return a raw pointer to the object this shared pointer points to.*
- `T * release ()` noexcept  
*Release the shared pointer without removing the reference.*

### 15.46.1 Detailed Description

```
template<typename T = void, template< typename X > class CNT = Default_ref_counter>
class cxx::Ref_ptr< T, CNT >
```

A reference-counting pointer with automatic cleanup.

## Template Parameters

<i>T</i>	Type of object the pointer points to.
<i>CNT</i>	Type of management class that manages the life time of the object.

This pointer is similar to the standard C++-11 `shared_ptr` but it does the reference counting directly in the object being pointed to, so that no additional management structures need to be allocated from the heap.

Classes that use this pointer type must implement two functions:

```
int remove_ref()
```

is called when a reference is removed and must return 0 when there are no further references to the object.

```
void add_ref()
```

is called when another `ref_ptr` to the object is created.

`Ref_obj` provides a simple implementation of this interface from which classes may inherit.

## Examples

[tmpfs/lib/src/fs.cc](#).

Definition at line 70 of file [ref\\_ptr](#).

## 15.46.2 Constructor & Destructor Documentation

### 15.46.2.1 Ref\_ptr() [1/3]

```
template<typename T = void, template< typename X > class CNT = Default_ref_counter>
cxx::Ref_ptr< T, CNT >::Ref_ptr (
    Wp const & o) [inline], [noexcept]
```

Create a shared pointer from a weak pointer.

Increases references.

Definition at line 88 of file [ref\\_ptr](#).

### 15.46.2.2 Ref\_ptr() [2/3]

```
template<typename T = void, template< typename X > class CNT = Default_ref_counter>
template<typename X>
cxx::Ref_ptr< T, CNT >::Ref_ptr (
    X * o) [inline], [explicit], [noexcept]
```

Create a shared pointer from a raw pointer.

In contrast to C++11 `shared_ptr` it is safe to use this constructor multiple times and have the same reference counter.

Definition at line 101 of file [ref\\_ptr](#).

**15.46.2.3 Ref\_ptr()** [3/3]

```
template<typename T = void, template< typename X > class CNT = Default_ref_counter>
cxx::Ref_ptr< T, CNT >::Ref_ptr (
    T * o,
    bool d) [inline], [noexcept]
```

Create a shared pointer from a raw pointer without creating a new reference.

**Parameters**

<i>o</i>	Pointer to the object.
<i>d</i>	Dummy parameter to select this constructor at compile time. The value may be true or false.

This is the counterpart to [release\(\)](#).

Definition at line 114 of file [ref\\_ptr](#).

**15.46.3 Member Function Documentation****15.46.3.1 get()**

```
template<typename T = void, template< typename X > class CNT = Default_ref_counter>
T * cxx::Ref_ptr< T, CNT >::get () const [inline], [noexcept]
```

Return a raw pointer to the object this shared pointer points to.

This does not release the pointer or decrease the reference count.

Definition at line 121 of file [ref\\_ptr](#).

**15.46.3.2 ptr()**

```
template<typename T = void, template< typename X > class CNT = Default_ref_counter>
T * cxx::Ref_ptr< T, CNT >::ptr () const [inline], [noexcept]
```

Return a raw pointer to the object this shared pointer points to.

This does not release the pointer or decrease the reference count.

Definition at line 127 of file [ref\\_ptr](#).

**15.46.3.3 release()**

```
template<typename T = void, template< typename X > class CNT = Default_ref_counter>
T * cxx::Ref_ptr< T, CNT >::release () [inline], [noexcept]
```

Release the shared pointer without removing the reference.

**Returns**

A raw pointer to the managed object.


Definition at line 138 of file [ref\\_ptr](#).

The documentation for this class was generated from the following file:

- I4/cxx/ref\_ptr



Collaboration diagram for cxx::S\_list< T, POLICY >:



### Public Member Functions

- void **add** (T \*e)  
*Add an element to the front of the list.*
- void **push\_front** (T \*e)  
*Add an element to the front of the list.*
- T \* **pop\_front** ()  
*Remove and return the head element of the list.*

**Public Member Functions inherited from****cxx::Bits::Basic\_list< Bits::Basic\_list\_policy< T, S\_list\_item > >**

- bool **empty** () const  
*Check if the list is empty.*
- Value\_type **front** () const  
*Return the first element in the list.*
- void **clear** ()  
*Remove all elements from the list.*
- Iterator **begin** ()  
*Return an iterator to the beginning of the list.*
- Const\_iterator **end** () const  
*Return a const iterator to the end of the list.*

**Additional Inherited Members****Static Public Member Functions inherited from****cxx::Bits::Basic\_list< Bits::Basic\_list\_policy< T, S\_list\_item > >**

- static Const\_iterator **iter** (Const\_value\_type c)  
*Return a const iterator that begins at the given element.*

**Protected Attributes inherited from****cxx::Bits::Basic\_list< Bits::Basic\_list\_policy< T, S\_list\_item > >**

- Bits::Basic\_list\_policy< T, S\_list\_item >::Head\_type \_f  
*Pointer to front of the list.*

**15.47.1 Detailed Description**

```
template<typename T, typename POLICY = Bits::Basic_list_policy< T, S_list_item >>
class cxx::S_list< T, POLICY >
```

Simple single-linked list.

**Template Parameters**

<i>T</i>	Type of elements saved in the list. Must inherit from cxx::S_list_item
----------	--

Definition at line 40 of file [slist](#).

## 15.47.2 Member Function Documentation

### 15.47.2.1 `pop_front()`

```
template<typename T, typename POLICY = Bits::Basic_list_policy< T, S_list_item >>
T * cxx::S_list< T, POLICY >::pop_front () [inline]
```

Remove and return the head element of the list.

#### Precondition

The list must not be empty or the behaviour will be undefined.

Definition at line 89 of file `slist`.

The documentation for this class was generated from the following file:


- `l4/cxx/slist`

## 15.48 `cxx::Slab< Type, Slab_size, Max_free, Alloc >` Class Template Reference

`Slab` allocator for object of type `Type`.


```
#include <slab_alloc>
```

Inheritance diagram for `cxx::Slab< Type, Slab_size, Max_free, Alloc >`:





Collaboration diagram for cxx::Slab< Type, Slab\_size, Max\_free, Alloc >:



### Public Member Functions

- `Type * alloc ()` noexcept  
*Allocate an object of type `Type`.*
- `void free (Type *o)` noexcept  
*Free the object addressed by `o`.*

## Public Member Functions inherited from

[cxx::Base\\_slab< sizeof\(Type\), L4\\_PAGESIZE, 2, New\\_allocator >](#)

- void \* [alloc](#) () noexcept  
*Allocate a new object.*
- void [free](#) (void \* \_o) noexcept  
*Free the given object (\_o).*
- unsigned [total\\_objects](#) () const noexcept  
*Get the total number of objects managed by the slab allocator.*
- unsigned [free\\_objects](#) () const noexcept  
*Get the number of objects which can be allocated before a new empty slab needs to be added to the slab allocator.*

## Additional Inherited Members

## Public Types inherited from

[cxx::Base\\_slab< sizeof\(Type\), L4\\_PAGESIZE, 2, New\\_allocator >](#)

- typedef [New\\_allocator](#)< Slab\_i > [Slab\\_alloc](#)  
*Type of the backend allocator.*

## 15.48.1 Detailed Description

```
template<typename Type, int Slab_size = L4_PAGESIZE, int Max_free = 2, template< typename A > class
Alloc = New_allocator>
class cxx::Slab< Type, Slab_size, Max_free, Alloc >
```

[Slab](#) allocator for object of type `Type`.

### Template Parameters

<i>Type</i>	The type of the objects to manage.
<i>Slab_size</i>	Size of a slab.
<i>Max_free</i>	The maximum number of free slabs.
<i>Alloc</i>	The allocator for the slabs.

Definition at line 335 of file [slab\\_alloc](#).

## 15.48.2 Member Function Documentation

### 15.48.2.1 alloc()

```
template<typename Type, int Slab_size = L4_PAGESIZE, int Max_free = 2, template< typename A >
class Alloc = New_allocator>
Type * cxx::Slab< Type, Slab\_size, Max\_free, Alloc >::alloc () [inline], [noexcept]
```

Allocate an object of type `Type`.

**Returns**

A pointer to the object just allocated, or 0 on failure.


**Note**

The user is responsible for initializing the object.

Definition at line 355 of file `slab_alloc`.

References `cxx::Base_slab< sizeof(Type), Slab_size, Max_free, Alloc >::alloc()`.

Here is the call graph for this function:

**15.48.2.2 free()**

```

template<typename Type, int Slab_size = L4_PAGESIZE, int Max_free = 2, template< typename A >
class Alloc = New_allocator>
void cxx::Slab< Type, Slab_size, Max_free, Alloc >::free (
    Type * o) [inline], [noexcept]
  
```

Free the object addressed by `o`.

**Parameters**

<code>o</code>	The pointer to the object to free.
----------------	------------------------------------

**Precondition**

The object must have been allocated with this allocator.

Definition at line 366 of file `slab_alloc`.


References `free()`.

Referenced by `free()`.

Here is the call graph for this function:



Here is the caller graph for this function:



The documentation for this class was generated from the following file:


- `I4/cxx/slab_alloc`

## 15.49 `cxx::Slab_static< Type, Slab_size, Max_free, Alloc > Class` Template Reference


Merged slab allocator (allocators for objects of the same size are merged together).

```
#include <slab_alloc>
```

Inheritance diagram for cxx::Slab\_static< Type, Slab\_size, Max\_free, Alloc >:



Collaboration diagram for `cxx::Slab_static< Type, Slab_size, Max_free, Alloc >`:



### Public Member Functions

- `Type * alloc () noexcept`  
Allocate an object of type *Type*.

### Public Member Functions inherited from

`cxx::Base_slab_static< sizeof(Type), L4_PAGESIZE, 2, New_allocator >`

- `void * alloc () noexcept`

*Allocate an object.*

- void `free` (void \*p) noexcept

*Free the given object (p).*

- unsigned `total_objects` () const noexcept

*Get the total number of objects managed by the slab allocator.*

- unsigned `free_objects` () const noexcept

*Get the number of free objects in the slab allocator.*

## Additional Inherited Members

## Public Types inherited from

`cxx::Base_slab_static< sizeof(Type), L4_PAGESIZE, 2, New_allocator >`

## 15.49.1 Detailed Description

```
template<typename Type, int Slab_size = L4_PAGESIZE, int Max_free = 2, template< typename A > class
Alloc = New_allocator>
```

```
class cxx::Slab_static< Type, Slab_size, Max_free, Alloc >
```

Merged slab allocator (allocators for objects of the same size are merged together).

## Template Parameters

<i>Type</i>	The type of the objects to manage.
<i>Slab_size</i>	The size of a slab.
<i>Max_free</i>	The maximum number of free slabs.
<i>Alloc</i>	The allocator for the slabs.

This slab allocator class is useful for merging slab allocators with the same parameters (equal `sizeof(Type)`, `Slab_size`, `Max_free`, and `Alloc` parameters) together and share the overhead for the slab caches among all equal-sized objects.

Definition at line 465 of file `slab_alloc`.

## 15.49.2 Member Function Documentation

### 15.49.2.1 `alloc()`

```
template<typename Type, int Slab_size = L4_PAGESIZE, int Max_free = 2, template< typename A >
class Alloc = New_allocator>
Type * cxx::Slab_static< Type, Slab_size, Max_free, Alloc >::alloc () [inline], [noexcept]
```

Allocate an object of type `Type`.

## Returns

A pointer to the just allocated object, or 0 on failure.

**Note**


The object is not zeroed out by the slab allocator.

Definition at line 478 of file [slab\\_alloc](#).


References [alloc\(\)](#).

Referenced by [alloc\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



The documentation for this class was generated from the following file:

- `l4/cxx/slab_alloc`


## 15.50 `cxx::static_vector< T, IDX >` Class Template Reference

Simple encapsulation for a dynamically allocated array.

```
#include <static_vector>
```



Collaboration diagram for `cxx::static_vector< T, IDX >`:



### Public Member Functions

- `template<typename X, typename = enable_if_t<is_convertible<X, T>::value>>`  
**static\_vector** (`static_vector< X, IDX > const &o`)  
*Conversion from compatible arrays.*
- `index_type` **index** (`value_type const *o`) `const`  
*Get the index of the given element of the array.*

### 15.50.1 Detailed Description

```
template<typename T, typename IDX = unsigned>
class cxx::static_vector< T, IDX >
```

Simple encapsulation for a dynamically allocated array.

The main purpose of this class is to support C++11 range for simple dynamically allocated array with static size.

Definition at line 16 of file [static\\_vector](#).

The documentation for this class was generated from the following file:


- `l4/cxx/static_vector`

## 15.51 cxx::String Class Reference

Allocation free string class with explicit length field.

```
#include <string>
```

Inheritance diagram for `cxx::String`:



Collaboration diagram for cxx::String:

cxx::String
<ul style="list-style-type: none"> <li>+ String()</li> <li>+ String()</li> <li>+ String()</li> <li>+ String()</li> <li>+ start()</li> <li>+ end()</li> <li>+ len()</li> <li>+ start()</li> <li>+ len()</li> <li>+ empty()</li> <li>and 19 more...</li> </ul>

## Public Types

- typedef char const \* **Index**  
*Character index type.*

## Public Member Functions

- **String** (char const \*s) noexcept  
*Initialize from a zero-terminated string.*
- **String** (char const \*s, unsigned long len) noexcept  
*Initialize from a pointer to first character and a length.*
- **String** (char const \*s, char const \*e) noexcept  
*Initialize with start and end pointer.*
- **String** ()  
*Zero-initialize. Create an invalid string.*
- **Index start** () const  
*Pointer to first character.*
- **Index end** () const  
*Pointer to first byte behind the string.*
- int **len** () const  
*Length.*
- void **start** (char const \*s)  
*Set start.*
- void **len** (unsigned long len)

- Set length.*
- **bool empty ()** const
  - Check if the string has length zero.*
- **String head (Index end)** const
  - Return prefix up to index.*
- **String head** (unsigned long end) const
  - Prefix of length end.*
- **String substr** (unsigned long idx, unsigned long len=`~0UL`) const
  - Substring of length len starting at idx.*
- **String substr** (char const \*start, unsigned long len=0) const
  - Substring of length len starting at start.*
- **template<typename F>**
  - char const \* find\_match** (F &&match) const
    - Find matching character. match should be a function such as isspace.*
- **char const \* find** (char const \*c) const
  - Find character. Return end() if not found.*
- **char const \* find** (int c) const
  - Find character. Return end() if not found.*
- **char const \* rfind** (char const \*c) const
  - Find right-most character. Return end() if not found.*
- **Index starts\_with** (cxx::String const &c) const
  - Check if c is a prefix of string.*
- **char const \* find** (int c, char const \*s) const
  - Find character c starting at position s. Return end() if not found.*
- **char const \* find** (char const \*c, char const \*s) const
  - Find character set at position.*
- **char const & operator[]** (unsigned long idx) const
  - Get character at idx.*
- **char const & operator[]** (int idx) const
  - Get character at idx.*
- **char const & operator[]** (Index idx) const
  - Get character at idx.*
- **bool eof** (char const \*s) const
  - Check if pointer s points behind string.*
- **template<typename INT>**
  - int from\_dec** (INT \*v) const
    - Convert decimal string to integer.*
- **template<typename INT>**
  - int from\_hex** (INT \*v) const
    - Convert hex string to integer.*
- **bool operator==** (String const &o) const
  - Equality.*
- **bool operator!=** (String const &o) const
  - Inequality.*

### 15.51.1 Detailed Description

Allocation free string class with explicit length field.

This class is used to group characters of a string which belong to one syntactical token types number, identifier, string, whitespace or another single character.

Stings in this class can contain null bytes and may denote parts of other strings.

#### Examples

[tmpfs/lib/src/fs.cc](#).

Definition at line 30 of file [string](#).

### 15.51.2 Constructor & Destructor Documentation

#### 15.51.2.1 String()

```
cxx::String::String (  
    char const * s,  
    char const * e) [inline], [noexcept]
```

Initialize with start and end pointer.

#### Parameters

<i>s</i>	first character of the string
<i>e</i>	pointer to first byte behind the string

Definition at line 48 of file [string](#).

### 15.51.3 Member Function Documentation

#### 15.51.3.1 find()

```
char const * cxx::String::find (  
    char const * c,  
    char const * s) const [inline]
```

Find character set at position.

#### Parameters

<i>c</i>	zero-terminated string of characters to search for
<i>s</i>	start position of search in string


**Return values**

<a href="#">end()</a>	if no char in <code>c</code> is contained in string at or behind <code>s</code> .
<i>position</i>	in string of some character in <code>c</code> .

Definition at line 191 of file [string](#).

References [end\(\)](#), and [eof\(\)](#).

Here is the call graph for this function:

**15.51.3.2 from\_dec()**

```

template<typename INT>
int cxx::String::from_dec (
    INT * v) const [inline]
  
```

Convert decimal string to integer.

**Template Parameters**

<i>INT</i>	result integer type
------------	---------------------

**Parameters**

<i>out</i>	<i>v</i>	conversion result
------------	----------	-------------------


**Returns**

position of first character not converted.

Definition at line 228 of file [string](#).

References [eof\(\)](#), and [start\(\)](#).

Here is the call graph for this function:



### 15.51.3.3 from\_hex()

```
template<typename INT>  
int cxx::String::from_hex (  
    INT * v) const [inline]
```

Convert hex string to integer.

#### Template Parameters

<i>INT</i>	result integer type
------------	---------------------

#### Parameters

out	<i>v</i>	conversion result
-----	----------	-------------------


#### Return values

<i>-1</i>	if the maximal amount of digits fitting into <code>INT</code> have been read,
<i>position</i>	of first character not converted otherwise.

Definition at line 257 of file [string](#).

References [eof\(\)](#), and [start\(\)](#).

Here is the call graph for this function:



#### 15.51.3.4 starts\_with()

```
Index cxx::String::starts_with (  
    cxx::String const & c) const [inline]
```

Check if `c` is a prefix of string.


##### Returns

0 if `c` is not a prefix, if it is a prefix, return first position not in `c` (which might be `end()`).

Definition at line 155 of file `string`.

References `start()`.

Here is the call graph for this function:



The documentation for this class was generated from the following file:

- `I4/cxx/string`




## 15.52 cxx::Weak\_ref< T > Class Template Reference


Typed weak reference to an object of type T.

```
#include <weak_ref>
```

Inheritance diagram for cxx::Weak\_ref< T >:



Collaboration diagram for `cxx::Weak_ref< T >`:



#### Additional Inherited Members

#### Public Member Functions inherited from `cxx::H_list_item_t< Weak_ref_base >`

- `H_list_item_t()`  
*Constructor.*
- `~H_list_item_t()` noexcept  
*Destructor.*

### 15.52.1 Detailed Description

```
template<typename T>
class cxx::Weak_ref< T >
```

Typed weak reference to an object of type `T`.

#### Template Parameters

<code>T</code>	The type of the referenced object.
----------------	------------------------------------

A weak reference is a reference that is invalidated when the referenced object is about to be deleted. All weak references to an object are kept in a linked list (see [Weak\\_ref\\_base::List](#)) and all the weak references are iterated and reset by the [Weak\\_ref\\_base::List](#) destructor or `Weak_ref_base::List::reset()`.

The type `T` must provide two methods that handle the housekeeping of weak references: `remove_weak_ref(Weak_ref_base *)` and `add_weak_ref(Weak_ref_base *)`. These functions must handle the insertion and removal of the weak reference into the respective [Weak\\_ref\\_base::List](#) object. For convenience one can use the `cxx::Weak_ref_obj` as a base class that handles weak references for you.

For example:

```
class C : public cxx::Weak_ref_obj {};

int main()
{
    cxx::Weak_ref<C> r; // r is nullptr
    {
        C c;
        r = &c; // now r points to c
    } // c is destructed, which implies resetting all weak references to c
    // now r is nullptr
    return 0;
}
```

#### Note

Weak references have no effect on the lifetime of the referenced object. Hence, a referenced object is *not* deleted when all weak references for it are gone. If automatic deletion is needed, see [cxx::Ref\\_ptr](#).

Definition at line 95 of file [weak\\_ref](#).

The documentation for this class was generated from the following file:


- `I4/cxx/weak_ref`

## 15.53 cxx::Weak\_ref\_base Class Reference


Generic (base) weak reference to some object.

```
#include <weak_ref>
```

Inheritance diagram for `cxx::Weak_ref_base`:



Collaboration diagram for cxx::Weak\_ref\_base:



## Data Structures

- struct [List](#)

*The list type for keeping all weak references to an object.*

## Additional Inherited Members

## Public Member Functions inherited from [cxx::H\\_list\\_item\\_t< Weak\\_ref\\_base >](#)

- [H\\_list\\_item\\_t](#) ()  
*Constructor.*
- [~H\\_list\\_item\\_t](#) () noexcept  
*Destructor.*

### 15.53.1 Detailed Description

Generic (base) weak reference to some object.

A weak reference is a reference that gets reset to NULL when the object shall be deleted. All weak references to the same object are kept in a linked list of weak references.

For typed weak references see [cxx::Weak\\_ref](#).

Definition at line 24 of file [weak\\_ref](#).

The documentation for this class was generated from the following file:


- I4/cxx/weak\_ref

## 15.54 cxx::Weak\_ref\_base::List Struct Reference


The list type for keeping all weak references to an object.

```
#include <weak_ref>
```

Inheritance diagram for cxx::Weak\_ref\_base::List:



Collaboration diagram for `cxx::Weak_ref_base::List`:



### Additional Inherited Members

### Public Member Functions inherited from

**`cxx::H_list< Weak_ref_base, Bits::Basic_list_policy< Weak_ref_base, H_list_item_t< Weak_ref_base > > >`**

- `void add (Weak_ref_base *e)`



- *Add element to the front of the list.*
- void **push\_front** (`Weak_ref_base *e`)  
*Add element to the front of the list.*
- `Weak_ref_base * pop_front` ()  
*Remove and return the head element of the list.*
- Iterator **insert** (`Weak_ref_base *e`, Iterator const &pred)  
*Insert an element at the iterator position.*

### Public Member Functions inherited from

`cxx::Bits::Basic_list< Bits::Basic_list_policy< Weak_ref_base, H_list_item_t< Weak_ref_base > > >`

- bool **empty** () const  
*Check if the list is empty.*
- Value\_type **front** () const  
*Return the first element in the list.*
- void **clear** ()  
*Remove all elements from the list.*
- Iterator **begin** ()  
*Return an iterator to the beginning of the list.*
- Const\_iterator **end** () const  
*Return a const iterator to the end of the list.*

### Static Public Member Functions inherited from

`cxx::H_list< Weak_ref_base, Bits::Basic_list_policy< Weak_ref_base, H_list_item_t< Weak_ref_base > > >`

- static Iterator **iter** (`Weak_ref_base *c`)  
*Return an iterator for an arbitrary list element.*
- static bool **in\_list** (`Weak_ref_base const *e`)  
*Check if the given element is currently part of a list.*
- static Iterator **insert\_after** (`Weak_ref_base *e`, Iterator const &pred)  
*Insert an element after the iterator position.*
- static void **insert\_before** (`Weak_ref_base *e`, Iterator const &succ)  
*Insert an element before the iterator position.*
- static void **replace** (`Weak_ref_base *p`, `Weak_ref_base *e`)  
*Replace an element in a list with a new element.*
- static void **remove** (`Weak_ref_base *e`)  
*Remove the given element from its list.*
- static Iterator **erase** (Iterator const &e)  
*Remove the element at the given iterator position.*

### Static Public Member Functions inherited from

`cxx::Bits::Basic_list< Bits::Basic_list_policy< Weak_ref_base, H_list_item_t< Weak_ref_base > > >`

- static Const\_iterator **iter** (Const\_value\_type c)  
*Return a const iterator that begins at the given element.*

**Protected Attributes inherited from**

[cxx::Bits::Basic\\_list](#)< [Bits::Basic\\_list\\_policy](#)< [Weak\\_ref\\_base](#), [H\\_list\\_item\\_t](#)< [Weak\\_ref\\_base](#) > > >

- [Bits::Basic\\_list\\_policy](#)< [Weak\\_ref\\_base](#), [H\\_list\\_item\\_t](#)< [Weak\\_ref\\_base](#) > >::Head\_type\_f  
*Pointer to front of the list.*

**15.54.1 Detailed Description**

The list type for keeping all weak references to an object.

On destruction of a list, all weak references to the respective object are set to `nullptr`.

Definition at line 38 of file [weak\\_ref](#).

The documentation for this struct was generated from the following file:


- `l4/cxx/weak_ref`

**15.55 Elf32\_Auxv Struct Reference**

Auxiliary vector (32-bit).

```
#include <elf.h>
```

Collaboration diagram for Elf32\_Auxv:

**Data Fields**

- [Elf32\\_Word atype](#)

**15.55.1 Detailed Description**

Auxiliary vector (32-bit).

Definition at line 963 of file [elf.h](#).

## 15.55.2 Field Documentation

### 15.55.2.1 atype

`Elf32_Word Elf32_Auxv::atype`

See also

[Elf\\_ATs](#)

Definition at line 965 of file [elf.h](#).

The documentation for this struct was generated from the following file:


- [l4/util/elf.h](#)

## 15.56 Elf32\_Dyn Struct Reference

ELF32 dynamic entry.

```
#include <elf.h>
```

Collaboration diagram for Elf32\_Dyn:



### Data Fields

- [Elf32\\_Sword d\\_tag](#)

### 15.56.1 Detailed Description

ELF32 dynamic entry.

Definition at line 513 of file [elf.h](#).

## 15.56.2 Field Documentation

### 15.56.2.1 d\_tag

[Elf32\\_Sword](#) Elf32\_Dyn::d\_tag

See also

[Elf\\_DTs](#)

Definition at line 515 of file [elf.h](#).

The documentation for this struct was generated from the following file:

- [l4/util/elf.h](#)

## 15.57 Elf32\_Ehdr Struct Reference

ELF32 header.

```
#include <elf.h>
```

Collaboration diagram for Elf32\_Ehdr:

Elf32_Ehdr
+ e_ident
+ e_type
+ e_machine
+ e_version
+ e_entry
+ e_phoff
+ e_shoff
+ e_flags
+ e_ehsize
+ e_phentsize
+ e_phnum
+ e_shentsize
+ e_shnum
+ e_shstrndx

**Data Fields**

- unsigned char **e\_ident** [[EI\\_NIDENT](#)]  
*see [Elf\\_EI](#)s*
- [Elf32\\_Half](#) **e\_type**  
*type of ELF file*
- [Elf32\\_Half](#) **e\_machine**  
*required architecture*
- [Elf32\\_Word](#) **e\_version**  
*file version*
- [Elf32\\_Addr](#) **e\_entry**  
*initial program counter*
- [Elf32\\_Off](#) **e\_phoff**  
*offset of program header table*
- [Elf32\\_Off](#) **e\_shoff**  
*offset of file header table*
- [Elf32\\_Word](#) **e\_flags**  
*processor-specific flags*
- [Elf32\\_Half](#) **e\_ehsize**  
*size of ELF header*
- [Elf32\\_Half](#) **e\_phentsize**  
*size of program header entry*
- [Elf32\\_Half](#) **e\_phnum**  
*number of entries in program header table*
- [Elf32\\_Half](#) **e\_shentsize**  
*size of section header entry*
- [Elf32\\_Half](#) **e\_shnum**  
*number of entries in section header table*
- [Elf32\\_Half](#) **e\_shstrndx**  
*section header table index of strtab*

**15.57.1 Detailed Description**

ELF32 header.

Definition at line [125](#) of file [elf.h](#).

**15.57.2 Field Documentation****15.57.2.1 e\_flags**

[Elf32\\_Word](#) [Elf32\\_Ehdr::e\\_flags](#)

processor-specific flags

See also

[Elf\\_EF\\_ARM\\_s](#)

Definition at line [134](#) of file [elf.h](#).

### 15.57.2.2 e\_machine

`Elf32_Half Elf32_Ehdr::e_machine`

required architecture

See also

[Elf\\_EMs](#)

Definition at line 129 of file [elf.h](#).

### 15.57.2.3 e\_type

`Elf32_Half Elf32_Ehdr::e_type`

type of ELF file

See also

[Elf\\_ETs](#)

Definition at line 128 of file [elf.h](#).

### 15.57.2.4 e\_version

`Elf32_Word Elf32_Ehdr::e_version`

file version

See also

[Elf\\_EVs](#)

Definition at line 130 of file [elf.h](#).

The documentation for this struct was generated from the following file:

- [l4/util/elf.h](#)

## 15.58 Elf32\_Phdr Struct Reference

Elf32 program header.

```
#include <elf.h>
```

Collaboration diagram for Elf32\_Phdr:

Elf32_Phdr
+ p_type
+ p_offset
+ p_vaddr
+ p_paddr
+ p_filesz
+ p_memsz
+ p_flags
+ p_align

### Data Fields

- [Elf32\\_Word p\\_type](#)  
*type of program section*
- [Elf32\\_Off p\\_offset](#)  
*file offset of program section*
- [Elf32\\_Addr p\\_vaddr](#)  
*memory address of prog section*
- [Elf32\\_Addr p\\_paddr](#)  
*physical address (ignored)*
- [Elf32\\_Word p\\_filesz](#)  
*file size of program section*
- [Elf32\\_Word p\\_memsz](#)  
*memory size of program section*
- [Elf32\\_Word p\\_flags](#)  
*flags*
- [Elf32\\_Word p\\_align](#)  
*alignment of section*

### 15.58.1 Detailed Description

Elf32 program header.

Definition at line 425 of file [elf.h](#).

## 15.58.2 Field Documentation

### 15.58.2.1 p\_flags

`Elf32_Word Elf32_Phdr::p_flags`

flags

See also

[Elf\\_PFs](#)

Definition at line [433](#) of file [elf.h](#).

### 15.58.2.2 p\_type

`Elf32_Word Elf32_Phdr::p_type`

type of program section

See also

[Elf\\_PTs](#)

Definition at line [427](#) of file [elf.h](#).

The documentation for this struct was generated from the following file:


- [l4/util/elf.h](#)

## 15.59 Elf32\_Rel Struct Reference

ELF32 relocation entry w/o addend.

```
#include <elf.h>
```

Collaboration diagram for Elf32\_Rel:





### 15.59.1 Detailed Description

ELF32 relocation entry w/o addend.

Definition at line 631 of file [elf.h](#).

The documentation for this struct was generated from the following file:


- [l4/util/elf.h](#)

## 15.60 Elf32\_Rela Struct Reference

ELF32 relocation entry w/ addend.

```
#include <elf.h>
```

Collaboration diagram for Elf32\_Rela:



### 15.60.1 Detailed Description

ELF32 relocation entry w/ addend.

Definition at line 638 of file [elf.h](#).

The documentation for this struct was generated from the following file:

- [l4/util/elf.h](#)

## 15.61 Elf32\_Shdr Struct Reference

ELF32 section header.

```
#include <elf.h>
```

Collaboration diagram for Elf32\_Shdr:

Elf32_Shdr
+ sh_name
+ sh_type
+ sh_flags
+ sh_addr
+ sh_offset
+ sh_size
+ sh_link
+ sh_info
+ sh_addralign
+ sh_entsize

### Data Fields

- [Elf32\\_Word](#) **sh\_name**  
*name of sect (idx into strtab)*
- [Elf32\\_Word](#) **sh\_type**  
*section's type*
- [Elf32\\_Word](#) **sh\_flags**  
*section's flags*
- [Elf32\\_Addr](#) **sh\_addr**  
*memory address of section*
- [Elf32\\_Off](#) **sh\_offset**  
*file offset of section*
- [Elf32\\_Word](#) **sh\_size**  
*file size of section*
- [Elf32\\_Word](#) **sh\_link**  
*idx to associated header section*
- [Elf32\\_Word](#) **sh\_info**  
*extra info of header section*
- [Elf32\\_Word](#) **sh\_addralign**  
*address alignment constraints*
- [Elf32\\_Word](#) **sh\_entsize**  
*size of entry if sect is table*

## 15.61.1 Detailed Description

ELF32 section header.

Definition at line 347 of file [elf.h](#).

## 15.61.2 Field Documentation

### 15.61.2.1 sh\_flags

[Elf32\\_Word](#) Elf32\_Shdr::sh\_flags

section's flags

See also

[Elf\\_SHFs](#)

Definition at line 351 of file [elf.h](#).

### 15.61.2.2 sh\_type

[Elf32\\_Word](#) Elf32\_Shdr::sh\_type

section's type

See also

[Elf\\_SHTs](#)

Definition at line 350 of file [elf.h](#).

The documentation for this struct was generated from the following file:

- [l4/util/elf.h](#)

## 15.62 Elf32\_Sym Struct Reference

ELF32 symbol table entry.

```
#include <elf.h>
```

Collaboration diagram for Elf32\_Sym:

Elf32_Sym
+ st_name
+ st_value
+ st_size
+ st_info
+ st_other
+ st_shndx

### Data Fields

- [Elf32\\_Word](#) **st\_name**  
*name of symbol (idx symstrtab)*
- [Elf32\\_Addr](#) **st\_value**  
*value of associated symbol*
- [Elf32\\_Word](#) **st\_size**  
*size of associated symbol*
- unsigned char **st\_info**  
*type and binding info*
- unsigned char **st\_other**  
*undefined*
- [Elf32\\_Half](#) **st\_shndx**  
*associated section header*

### 15.62.1 Detailed Description

ELF32 symbol table entry.

Definition at line 871 of file [elf.h](#).

The documentation for this struct was generated from the following file:


- [l4/util/elf.h](#)

## 15.63 Elf64\_Auxv Struct Reference

Auxiliary vector (64-bit).

```
#include <elf.h>
```

Collaboration diagram for Elf64\_Auxv:



### Data Fields

- [Elf64\\_Word atype](#)

### 15.63.1 Detailed Description

Auxiliary vector (64-bit).

Definition at line [970](#) of file [elf.h](#).

### 15.63.2 Field Documentation

#### 15.63.2.1 atype

```
Elf64_Word Elf64_Auxv::atype
```

See also

[Elf\\_ATs](#)

Definition at line [972](#) of file [elf.h](#).

The documentation for this struct was generated from the following file:


- [l4/util/elf.h](#)

## 15.64 Elf64\_Dyn Struct Reference

ELF64 dynamic entry.

```
#include <elf.h>
```

Collaboration diagram for Elf64\_Dyn:



### Data Fields

- [Elf64\\_Sxword d\\_tag](#)

### 15.64.1 Detailed Description

ELF64 dynamic entry.

Definition at line [524](#) of file [elf.h](#).

### 15.64.2 Field Documentation

#### 15.64.2.1 d\_tag

```
Elf64_Sxword Elf64_Dyn::d_tag
```

See also

[Elf\\_DTs](#)

Definition at line [526](#) of file [elf.h](#).

The documentation for this struct was generated from the following file:

- [l4/util/elf.h](#)

## 15.65 Elf64\_Ehdr Struct Reference

ELF64 header.

```
#include <elf.h>
```

Collaboration diagram for Elf64\_Ehdr:

Elf64_Ehdr
+ e_ident
+ e_type
+ e_machine
+ e_version
+ e_entry
+ e_phoff
+ e_shoff
+ e_flags
+ e_ehsize
+ e_phentsize
+ e_phnum
+ e_shentsize
+ e_shnum
+ e_shstrndx

### Data Fields

- unsigned char **e\_ident** [[EI\\_NIDENT](#)]  
*see [Elf\\_EI](#)s*
- [Elf64\\_Half](#) **e\_type**  
*type of ELF file*
- [Elf64\\_Half](#) **e\_machine**  
*required architecture*
- [Elf64\\_Word](#) **e\_version**  
*file version*
- [Elf64\\_Addr](#) **e\_entry**  
*initial program counter*
- [Elf64\\_Off](#) **e\_phoff**  
*offset of program header table*
- [Elf64\\_Off](#) **e\_shoff**

- offset of file header table*
- [Elf64\\_Word e\\_flags](#)  
*processor-specific flags*
- [Elf64\\_Half e\\_ehsize](#)  
*size of ELF header*
- [Elf64\\_Half e\\_phentsize](#)  
*size of program header entry*
- [Elf64\\_Half e\\_phnum](#)  
*number of entries in program header table*
- [Elf64\\_Half e\\_shentsize](#)  
*size of section header entry*
- [Elf64\\_Half e\\_shnum](#)  
*number of entries in section header table*
- [Elf64\\_Half e\\_shstrndx](#)  
*section header table index of strtab*

## 15.65.1 Detailed Description

ELF64 header.

Definition at line 146 of file [elf.h](#).

## 15.65.2 Field Documentation

### 15.65.2.1 e\_flags

```
Elf64_Word Elf64_Ehdr::e_flags
```

processor-specific flags

See also

[Elf\\_EF\\_ARM\\_s](#)

Definition at line 155 of file [elf.h](#).

### 15.65.2.2 e\_machine

```
Elf64_Half Elf64_Ehdr::e_machine
```

required architecture

See also

[Elf\\_EMs](#)

Definition at line 150 of file [elf.h](#).



### 15.65.2.3 e\_type

`Elf64_Half Elf64_Ehdr::e_type`

type of ELF file

See also

[Elf\\_ETs](#)

Definition at line 149 of file [elf.h](#).

### 15.65.2.4 e\_version

`Elf64_Word Elf64_Ehdr::e_version`

file version

See also

[Elf\\_EVs](#)

Definition at line 151 of file [elf.h](#).

The documentation for this struct was generated from the following file:

- [l4/util/elf.h](#)

## 15.66 Elf64\_Phdr Struct Reference

ELF64 program header.

```
#include <elf.h>
```

Collaboration diagram for Elf64\_Phdr:

Elf64_Phdr
+ p_type
+ p_flags
+ p_offset
+ p_vaddr
+ p_paddr
+ p_filesz
+ p_memsz
+ p_align

## Data Fields

- [Elf64\\_Word](#) **p\_type**  
*type of program section*
- [Elf64\\_Word](#) **p\_flags**  
*flags*
- [Elf64\\_Off](#) **p\_offset**  
*file offset of program section*
- [Elf64\\_Addr](#) **p\_vaddr**  
*memory address of prog section*
- [Elf64\\_Addr](#) **p\_paddr**  
*physical address (ignored)*
- [Elf64\\_Xword](#) **p\_filesz**  
*file size of program section*
- [Elf64\\_Xword](#) **p\_memsz**  
*memory size of program section*
- [Elf64\\_Xword](#) **p\_align**  
*alignment of section*

## 15.66.1 Detailed Description

ELF64 program header.

Definition at line [438](#) of file [elf.h](#).

## 15.66.2 Field Documentation

### 15.66.2.1 p\_flags

[Elf64\\_Word](#) `Elf64_Phdr::p_flags`

flags

See also

[Elf\\_PFs](#)

Definition at line [441](#) of file [elf.h](#).

### 15.66.2.2 p\_type

[Elf64\\_Word](#) `Elf64_Phdr::p_type`

type of program section

See also

[Elf\\_PT](#)s

Definition at line [440](#) of file [elf.h](#).

The documentation for this struct was generated from the following file:


- [l4/util/elf.h](#)

## 15.67 Elf64\_Rel Struct Reference

ELF64 relocation entry w/o addend.

```
#include <elf.h>
```

Collaboration diagram for Elf64\_Rel:



### 15.67.1 Detailed Description

ELF64 relocation entry w/o addend.

Definition at line [646](#) of file [elf.h](#).

The documentation for this struct was generated from the following file:


- [l4/util/elf.h](#)

## 15.68 Elf64\_Rela Struct Reference

ELF64 relocation entry w/ addend.

```
#include <elf.h>
```

Collaboration diagram for Elf64\_Rela:



### 15.68.1 Detailed Description

ELF64 relocation entry w/ addend.

Definition at line 653 of file [elf.h](#).

The documentation for this struct was generated from the following file:

- [l4/util/elf.h](#)

## 15.69 Elf64\_Shdr Struct Reference

ELF64 section header.

```
#include <elf.h>
```

Collaboration diagram for Elf64\_Shdr:

Elf64_Shdr
+ sh_name
+ sh_type
+ sh_flags
+ sh_addr
+ sh_offset
+ sh_size
+ sh_link
+ sh_info
+ sh_addralign
+ sh_entsize

### Data Fields

- [Elf64\\_Word](#) **sh\_name**  
*name of sect (idx into strtab)*
- [Elf64\\_Word](#) **sh\_type**  
*section's type*
- [Elf64\\_Xword](#) **sh\_flags**  
*section's flags*
- [Elf64\\_Addr](#) **sh\_addr**

- memory address of section*
  - [Elf64\\_Off](#) **sh\_offset**
    - file offset of section*
  - [Elf64\\_Xword](#) **sh\_size**
    - file size of section*
  - [Elf64\\_Word](#) **sh\_link**
    - idx to associated header section*
  - [Elf64\\_Word](#) **sh\_info**
    - extra info of header section*
  - [Elf64\\_Xword](#) **sh\_addralign**
    - address alignment constraints*
  - [Elf64\\_Xword](#) **sh\_entsize**
    - size of entry if sect is table*

## 15.69.1 Detailed Description

ELF64 section header.

Definition at line 362 of file [elf.h](#).

## 15.69.2 Field Documentation

### 15.69.2.1 sh\_flags

[Elf64\\_Xword](#) [Elf64\\_Shdr::sh\\_flags](#)

section's flags

See also

[Elf\\_SHFs](#)

Definition at line 366 of file [elf.h](#).

### 15.69.2.2 sh\_type

[Elf64\\_Word](#) [Elf64\\_Shdr::sh\\_type](#)

section's type

See also

[Elf\\_SHTs](#)

Definition at line 365 of file [elf.h](#).

The documentation for this struct was generated from the following file:

- [l4/util/elf.h](#)

## 15.70 Elf64\_Sym Struct Reference

ELF64 symbol table entry.

```
#include <elf.h>
```

Collaboration diagram for Elf64\_Sym:

Elf64_Sym
+ st_name
+ st_info
+ st_other
+ st_shndx
+ st_value
+ st_size

### Data Fields

- [Elf64\\_Word](#) **st\_name**  
*name of symbol (idx symstrtab)*
- unsigned char **st\_info**  
*type and binding info*
- unsigned char **st\_other**  
*undefined*
- [Elf64\\_Half](#) **st\_shndx**  
*associated section header*
- [Elf64\\_Addr](#) **st\_value**  
*value of associated symbol*
- [Elf64\\_Xword](#) **st\_size**  
*size of associated symbol*

### 15.70.1 Detailed Description

ELF64 symbol table entry.

Definition at line 882 of file [elf.h](#).

The documentation for this struct was generated from the following file:


- [l4/util/elf.h](#)

## 15.71 Enum\_bitops::Enable< T > Struct Template Reference


Check whether the given enum type opts in for the bitwise operators.

```
#include <types>
```

Inheritance diagram for Enum\_bitops::Enable< T >:



Collaboration diagram for Enum\_bitops::Enable< T >:



### 15.71.1 Detailed Description

```
template<typename T>  
struct Enum_bitops::Enable< T >
```

Check whether the given enum type opts in for the bitwise operators.

Definition at line 440 of file [types](#).

The documentation for this struct was generated from the following file:

- [l4/sys/cxx/types](#)


## 15.72 Enum\_bitops::Has\_marker< typename, typename > Struct Template Reference

Marker for the opt-in ADL function.


```
#include <types>
```



Inheritance diagram for Enum\_bitops::Has\_marker< typename, typename >:



Collaboration diagram for Enum\_bitops::Has\_marker< typename, typename >:



#### Additional Inherited Members

#### Public Types inherited from `L4::Types::Bool< false >`

- typedef `Bool< V > type`  
The meta type itself.

#### 15.72.1 Detailed Description

```
template<typename, typename = void>
struct Enum_bitops::Has_marker< typename, typename >
```

Marker for the opt-in ADL function.

Definition at line 431 of file `types`.

The documentation for this struct was generated from the following file:


- `l4/sys/cxx/types`

## 15.73 Enum\_bitops::Has\_marker< T, Void< decltype(enum\_bitops\_enable(declval< T >()))> > Struct Template Reference


Marker for the opt-in ADL function.

```
#include <types>
```

Inheritance diagram for Enum\_bitops::Has\_marker< T, Void< decltype(enum\_bitops\_enable(declval< T >()))> >:  
>:



Collaboration diagram for Enum\_bitops::Has\_marker< T, Void< decltype(enum\_bitops\_enable(declval< T >()))>> >:



### Additional Inherited Members

### Public Types inherited from **L4::Types::Bool< false >**

- typedef **Bool**< V > **type**  
The meta type itself.

## Public Types inherited from [L4::Types::Bool< true >](#)

- typedef [Bool](#)< V > **type**  
*The meta type itself.*

### 15.73.1 Detailed Description

```
template<typename T>
struct Enum_bitops::Has_marker< T, Void< decltype(enum_bitops_enable(declval< T >()))> >
```

Marker for the opt-in ADL function.

Definition at line [435](#) of file [types](#).

The documentation for this struct was generated from the following file:


- [l4/sys/cxx/types](#)

## 15.74 L4::Alloc\_list Class Reference

A simple list-based allocator.

```
#include <alloc.h>
```

Collaboration diagram for L4::Alloc\_list:



### 15.74.1 Detailed Description

A simple list-based allocator.

Definition at line [20](#) of file [alloc.h](#).

The documentation for this class was generated from the following file:


- [l4/cxx/alloc.h](#)

## 15.75 L4::Arm\_smccc Class Reference

Wrapper for function calls that follow the ARM SMC/HVC calling convention.

```
#include <arm_smccc>
```

Collaboration diagram for L4::Arm\_smccc:



### Public Member Functions

- [l4\\_msgtag\\_t](#) [call](#) ([l4\\_umword\\_t](#) func, [l4\\_umword\\_t](#) in0, [l4\\_umword\\_t](#) in1, [l4\\_umword\\_t](#) in2, [l4\\_umword\\_t](#) in3, [l4\\_umword\\_t](#) in4, [l4\\_umword\\_t](#) in5, [l4\\_umword\\_t](#) \*out0, [l4\\_umword\\_t](#) \*out1, [l4\\_umword\\_t](#) \*out2, [l4\\_umword\\_t](#) \*out3, [l4\\_umword\\_t](#) client\_id)

*ARM SMC/HVC function call.*

### 15.75.1 Detailed Description

Wrapper for function calls that follow the ARM SMC/HVC calling convention.

See [l4\\_arm\\_smccc\\_call\(\)](#) for the corresponding C interface.

Definition at line 23 of file [arm\\_smccc](#).

## 15.75.2 Member Function Documentation

### 15.75.2.1 call()

```

l4_msgtag_t L4::Arm_smccc::call (
    l4_umword_t func,
    l4_umword_t in0,
    l4_umword_t in1,
    l4_umword_t in2,
    l4_umword_t in3,
    l4_umword_t in4,
    l4_umword_t in5,
    l4_umword_t * out0,
    l4_umword_t * out1,
    l4_umword_t * out2,

```

```

14_umword_t * out3,
14_umword_t client_id)

```

ARM SMC/HVC function call.

The input parameters consist of a function identifier, 6 arguments and a client id. Results are returned in 4 output parameters.

### Parameters

	<i>func</i>	Function identifier. <ul style="list-style-type: none"> <li>• Bit 31 has to be set: This marks the call as <i>Fast Call</i>. <i>Yielding Calls</i> (bit 31 unset) are rejected by the kernel.</li> <li>• Bit 30 defines the calling convention:</li> <li>• Bit 30 == 1: 64-bit calling convention.</li> <li>• Bit 30 == 0: 32-bit calling convention.</li> <li>• Bits 24..29 determine the service call ID. The permitted IDs are set in the kernel configuration. By default only service IDs <math>\geq 0x30000000</math> (<i>Trusted Application Calls</i> and <i>Trusted OS Calls</i>) are allowed.</li> </ul>
in	<i>in0</i>	First input parameter.
in	<i>in1</i>	Second input parameter.
in	<i>in2</i>	Third input parameter.
in	<i>in3</i>	Fourth input parameter.
in	<i>in4</i>	Fifth input parameter.
in	<i>in5</i>	Sixth input parameter.
out	<i>out0</i>	First output parameter.
out	<i>out1</i>	Second output parameter.
out	<i>out2</i>	Third output parameter.
out	<i>out3</i>	Fourth output parameter.
in	<i>client_id</i>	Client ID. According to the specification, this value might be ignored by certain functions.

### Return values

-L4_ENOSYS	Either bit 31 of the function call not set or service ID outside the range permitted by kernel configuration.
-L4_EINVAL	Invalid number of parameters.
< 0	Other <a href="#">L4</a> error.
0	Success.

The documentation for this class was generated from the following file:


- [l4/sys/arm\\_smccc](#)

## 15.76 L4::Base\_exception Class Reference

Base class for all exceptions, thrown by the [L4Re](#) framework.


```
#include <l4/cxx/exceptions>
```

Inheritance diagram for L4::Base\_exception:





Collaboration diagram for L4::Base\_exception:



### Public Member Functions

- virtual char const \* **str** () const noexcept=0  
*Return a human readable string for the exception.*
- virtual ~**Base\_exception** () noexcept  
*Destruction.*

### Public Member Functions inherited from [L4::Exception\\_tracer](#)

- void const \*const \* **pc\_array** () const noexcept  
*Get the array containing the call trace.*
- int **frame\_count** () const noexcept  
*Get the number of entries that are valid in the call trace.*

### Protected Member Functions

- **Base\_exception** () noexcept  
*Create a base exception.*

### Protected Member Functions inherited from [L4::Exception\\_tracer](#)

- **Exception\_tracer** () noexcept  
*Create a back trace.*

### 15.76.1 Detailed Description

Base class for all exceptions, thrown by the [L4Re](#) framework.

This is the abstract base of all exceptions thrown within the [L4Re](#) framework. It is basically also a good idea to use it as base of all user defined exceptions.

Definition at line 105 of file [exceptions](#).

The documentation for this class was generated from the following file:


- [l4/cxx/exceptions](#)

## 15.77 L4::Basic\_registry Class Reference


This registry returns the corresponding server object based on the label of an [lpc\\_gate](#).

```
#include <ipc_epiface>
```

Inheritance diagram for L4::Basic\_registry:



Collaboration diagram for L4::Basic\_registry:



### Static Public Member Functions

- static Value \* [find](#) ([l4\\_umword\\_t](#) label)  
*Get the server object for an [lpc\\_gate](#) label.*
- static [l4\\_msgtag\\_t](#) [dispatch](#) ([l4\\_msgtag\\_t](#) tag, [l4\\_umword\\_t](#) label, [l4\\_utcb\\_t](#) \*utcb)  
*The dispatch function called by the server loop.*

## 15.77.1 Detailed Description

This registry returns the corresponding server object based on the label of an [lpc\\_gate](#).

Definition at line [529](#) of file [ipc\\_epiface](#).

## 15.77.2 Member Function Documentation

### 15.77.2.1 dispatch()

```

l4\_msgtag\_t L4::Basic_registry::dispatch (
    l4\_msgtag\_t tag,
    l4\_umword\_t label,
    l4\_utcb\_t * utcb) [inline], [static]
  
```

The dispatch function called by the server loop.

This function forwards the message to the server object identified by the given *label*.

#### Parameters

<i>tag</i>	The message tag used for the invocation.
<i>label</i>	The label used to find the object including the rights bits of the invoked capability.
<i>utcb</i>	The UTCB used for the invocation.


**Returns**

The return code from the object's dispatch function or `-L4_ENOENT` if the object does not exist.

Definition at line 554 of file [ipc\\_epiface](#).

References [L4::Epiface::dispatch\(\)](#), and [find\(\)](#).

Here is the call graph for this function:

**15.77.2.2 find()**

```
Value * L4::Basic_registry::find (
    l4_umword_t label) [inline], [static]
```

Get the server object for an [lpc\\_gate](#) label.

**Parameters**

<i>label</i>	The label usually stored in an <a href="#">lpc_gate</a> .
--------------	---


**Returns**

A pointer to the [Epiface](#) identified by the given label.

Definition at line 538 of file [ipc\\_epiface](#).

Referenced by [dispatch\(\)](#).

Here is the caller graph for this function:



The documentation for this class was generated from the following file:


- `l4/sys/cxx/ipc_epiface`

## 15.78 L4::Bounds\_error Class Reference


Access out of bounds.

```
#include <exceptions>
```

Inheritance diagram for L4::Bounds\_error:



Collaboration diagram for L4::Bounds\_error:



#### Additional Inherited Members

#### Public Member Functions inherited from [L4::Runtime\\_error](#)

- [Runtime\\_error](#) (long [err\\_no](#), char const \*extra=0) noexcept  
Create a new [Runtime\\_error](#).
- char const \* **str** () const noexcept override  
Return a human readable string for the exception.

- char const \* [extra\\_str](#) () const  
*Get the description text for this runtime error.*
- long [err\\_no](#) () const noexcept  
*Get the error value for this runtime error.*

### Public Member Functions inherited from [L4::Base\\_exception](#)

- virtual ~**Base\_exception** () noexcept  
*Destruction.*

### Public Member Functions inherited from [L4::Exception\\_tracer](#)

- void const \*const \* **pc\_array** () const noexcept  
*Get the array containing the call trace.*
- int **frame\_count** () const noexcept  
*Get the number of entries that are valid in the call trace.*

### Protected Member Functions inherited from [L4::Base\\_exception](#)

- **Base\_exception** () noexcept  
*Create a base exception.*

### Protected Member Functions inherited from [L4::Exception\\_tracer](#)

- **Exception\_tracer** () noexcept  
*Create a back trace.*

## 15.78.1 Detailed Description

Access out of bounds.

Definition at line 278 of file [exceptions](#).


The documentation for this class was generated from the following file:

- [l4/cxx/exceptions](#)





Collaboration diagram for L4::Cap< T >:



## Public Member Functions

- `template<typename O>`  
`Cap (Cap< O > const &o) noexcept`  
*Create a copy from o, supporting implicit type casting.*
- `Cap (Cap_type cap) noexcept`  
*Constructor to create an invalid capability selector.*

- [Cap](#) ([l4\\_default\\_caps\\_t](#) cap) noexcept  
*Initialize capability with one of the default capability selectors.*
- [Cap](#) ([l4\\_cap\\_idx\\_t](#) idx=[L4\\_INVALID\\_CAP](#)) noexcept  
*Initialize capability, defaults to the invalid capability selector.*
- [Cap](#) ([No\\_init\\_type](#)) noexcept  
*Create an uninitialized cap selector.*
- [Cap](#) [move](#) (Cap const &src) const  
*Move a capability to this cap slot.*
- [Cap](#) [copy](#) (Cap const &src) const  
*Copy a capability to this cap slot.*
- [T](#) \* [operator->](#) () const noexcept  
*Member access of a [T](#).*

## Public Member Functions inherited from [L4::Cap\\_base](#)

- [l4\\_cap\\_idx\\_t](#) [cap](#) () const noexcept  
*Return capability selector.*
- bool [is\\_valid](#) () const noexcept  
*Test whether the capability is a valid capability index (i.e., not [L4\\_INVALID\\_CAP](#)).*
- int [invalid\\_cap\\_error](#) () const noexcept  
*Return the transported error code in an invalid capability index.*
- [l4\\_fpage\\_t](#) [fpage](#) (unsigned rights=[L4\\_CAP\\_FPAGE\\_RWS](#)) const noexcept  
*Return flexpage for the capability.*
- [l4\\_umword\\_t](#) [snd\\_base](#) (unsigned grant=[L4\\_MAP\\_ITEM\\_MAP](#), [l4\\_cap\\_idx\\_t](#) base=[L4\\_INVALID\\_CAP](#)) const noexcept  
*Return send base.*
- bool [operator==](#) ([Cap\\_base](#) const &o) const noexcept  
*Test if two capabilities are equal.*
- bool [operator!=](#) ([Cap\\_base](#) const &o) const noexcept  
*Test if two capabilities are not equal.*
- [l4\\_msgtag\\_t](#) [validate](#) ([l4\\_utcb\\_t](#) \*u=[l4\\_utcb\(\)](#)) const noexcept  
*Check whether a capability is present (refers to an object).*
- [l4\\_msgtag\\_t](#) [validate](#) ([Cap](#)< [Task](#) > task, [l4\\_utcb\\_t](#) \*u=[l4\\_utcb\(\)](#)) const noexcept  
*Check whether a capability is present (refers to an object).*
- void [invalidate](#) () noexcept  
*Set this capability to invalid ([L4\\_INVALID\\_CAP](#)).*

## Static Public Member Functions

- template<typename From>  
static void [check\\_convertible\\_from](#) () noexcept  
*Perform the type conversion that needs to compile in order for a capability of type From to be convertible to one of type T.*
- template<typename From>  
static void [check\\_castable\\_from](#) () noexcept  
*Perform the type conversion that needs to compile in order for a capability of type From to be castable (via the correct cap\_cast) to one of type T.*

## Friends

- class [L4::Kobject](#)

### Additional Inherited Members

#### Public Types inherited from L4::Cap\_base

- enum [No\\_init\\_type](#) { [No\\_init](#) }  
*Special value for uninitialized capability objects.*
- enum [Cap\\_type](#) { [Invalid](#) = L4\_INVALID\_CAP }  
*Invalid capability type.*

#### Protected Member Functions inherited from L4::Cap\_base

- [Cap\\_base](#) ([l4\\_cap\\_idx\\_t](#) c) noexcept  
*Generate a capability from its C representation.*
- [Cap\\_base](#) ([Cap\\_type](#) cap) noexcept  
*Constructor to create an invalid capability.*
- [Cap\\_base](#) ([l4\\_default\\_caps\\_t](#) cap) noexcept  
*Initialize capability with one of the default capabilities.*
- [Cap\\_base](#) () noexcept  
*Create an uninitialized instance.*
- void [move](#) ([Cap\\_base](#) const &src) const  
*Replace this capability with the contents of `src`.*
- void [copy](#) ([Cap\\_base](#) const &src) const  
*Copy a capability.*

#### Protected Attributes inherited from L4::Cap\_base

- [l4\\_cap\\_idx\\_t\\_c](#)  
*The C representation of a capability selector.*

### 15.79.1 Detailed Description

```
template<typename T>
class L4::Cap< T >
```

C++ interface for capabilities.

#### Template Parameters

<a href="#">T</a>	Type of the object the capability points to.
-------------------	--

The C++ version of a capability is comparable to a pointer, in fact it is a kind of smart pointer for our kernel objects and the objects derived from the kernel objects ([L4::Kobject](#)).

Add

```
#include <l4/sys/capability>
```

to your code to use the capability interface.

#### Examples

[examples/clntsrv/src/client.cc](#), [examples/libs/l4re/c++/mem\\_alloc/ma+rm.cc](#), [examples/libs/l4re/c++/shared\\_ds/ds\\_clnt.cc](#), [examples/libs/l4re/c++/shared\\_ds/ds\\_srv.cc](#), [examples/libs/l4re/streammap/client.cc](#), and [examples/sys/migrate/thread\\_migrate](#)

Definition at line 223 of file [capability.h](#).

## 15.79.2 Constructor & Destructor Documentation

### 15.79.2.1 Cap() [1/4]

```
template<typename T>
template<typename O>
L4::Cap< T >::Cap (
    Cap< O > const & o) [inline], [noexcept]
```

Create a copy from *o*, supporting implicit type casting.

#### Parameters

<i>o</i>	The source selector that shall be copied (and casted).
----------	--

Definition at line 275 of file [capability.h](#).

### 15.79.2.2 Cap() [2/4]

```
template<typename T>
L4::Cap< T >::Cap (
    Cap_type cap) [inline], [noexcept]
```

Constructor to create an invalid capability selector.

#### Parameters

<i>cap</i>	Capability selector.
------------	----------------------

Definition at line 282 of file [capability.h](#).

### 15.79.2.3 Cap() [3/4]

```
template<typename T>
L4::Cap< T >::Cap (
    l4_default_caps_t cap) [inline], [noexcept]
```

Initialize capability with one of the default capability selectors.

#### Parameters

<i>cap</i>	Capability selector.
------------	----------------------

Definition at line 288 of file [capability.h](#).

**15.79.2.4 Cap()** [4/4]

```
template<typename T>
L4::Cap< T >::Cap (
    l4_cap_idx_t idx = L4_INVALID_CAP) [inline], [explicit], [noexcept]
```

Initialize capability, defaults to the invalid capability selector.

**Parameters**

<i>idx</i>	Capability selector.
------------	----------------------

Definition at line 294 of file [capability.h](#).

**15.79.3 Member Function Documentation****15.79.3.1 check\_castable\_from()**

```
template<typename T>
template<typename From>
void L4::Cap< T >::check_castable_from () [inline], [static], [noexcept]
```

Perform the type conversion that needs to compile in order for a capability of type From to be castable (via the correct `cap_cast`) to one of type T.

**Template Parameters**

<i>From</i>	Type to convert from
-------------	----------------------

Definition at line 264 of file [capability.h](#).

**15.79.3.2 check\_convertible\_from()**

```
template<typename T>
template<typename From>
void L4::Cap< T >::check_convertible_from () [inline], [static], [noexcept]
```

Perform the type conversion that needs to compile in order for a capability of type From to be convertible to one of type T.

**Template Parameters**

<i>From</i>	Type to convert from
-------------	----------------------

Definition at line 251 of file [capability.h](#).



Collaboration diagram for L4::Cap\_base:

L4::Cap_base
# _c
+ cap()
+ is_valid()
+ invalid_cap_error()
+ fpage()
+ snd_base()
+ operator==( )
+ operator!=( )
+ validate()
+ validate()
+ invalidate()
# Cap_base()
# Cap_base()
# Cap_base()
# Cap_base()
# move()
# copy()

## Public Types

- enum [No\\_init\\_type](#) { [No\\_init](#) }  
*Special value for uninitialized capability objects.*
- enum [Cap\\_type](#) { [Invalid](#) = L4\_INVALID\_CAP }  
*Invalid capability type.*

## Public Member Functions

- [l4\\_cap\\_idx\\_t](#) [cap](#) () const noexcept  
*Return capability selector.*
- bool [is\\_valid](#) () const noexcept  
*Test whether the capability is a valid capability index (i.e., not L4\_INVALID\_CAP).*
- int [invalid\\_cap\\_error](#) () const noexcept  
*Return the transported error code in an invalid capability index.*
- [l4\\_fpage\\_t](#) [fpage](#) (unsigned rights=[L4\\_CAP\\_FPAGE\\_RWS](#)) const noexcept  
*Return flexpage for the capability.*

- [l4\\_umword\\_t snd\\_base](#) (unsigned grant=[L4\\_MAP\\_ITEM\\_MAP](#), [l4\\_cap\\_idx\\_t](#) base=[L4\\_INVALID\\_CAP](#)) const noexcept  
*Return send base.*
- bool **operator==** ([Cap\\_base](#) const &o) const noexcept  
*Test if two capabilities are equal.*
- bool **operator!=** ([Cap\\_base](#) const &o) const noexcept  
*Test if two capabilities are not equal.*
- [l4\\_msgtag\\_t validate](#) ([l4\\_utcb\\_t](#) \*u=[l4\\_utcb](#)()) const noexcept  
*Check whether a capability is present (refers to an object).*
- [l4\\_msgtag\\_t validate](#) ([Cap](#)< [Task](#) > task, [l4\\_utcb\\_t](#) \*u=[l4\\_utcb](#)()) const noexcept  
*Check whether a capability is present (refers to an object).*
- void **invalidate** () noexcept  
*Set this capability to invalid ([L4\\_INVALID\\_CAP](#)).*

### Protected Member Functions

- [Cap\\_base](#) ([l4\\_cap\\_idx\\_t](#) c) noexcept  
*Generate a capability from its C representation.*
- **Cap\_base** ([Cap\\_type](#) cap) noexcept  
*Constructor to create an invalid capability.*
- [Cap\\_base](#) ([l4\\_default\\_caps\\_t](#) cap) noexcept  
*Initialize capability with one of the default capabilities.*
- **Cap\_base** () noexcept  
*Create an uninitialized instance.*
- void **move** ([Cap\\_base](#) const &src) const  
*Replace this capability with the contents of *src*.*
- void **copy** ([Cap\\_base](#) const &src) const  
*Copy a capability.*

### Protected Attributes

- [l4\\_cap\\_idx\\_t \\_c](#)  
*The C representation of a capability selector.*

## 15.80.1 Detailed Description

Base class for all kinds of capabilities.

#### Attention

This class is not for direct use, use [L4::Cap](#) instead.

This class contains all the things that are independent of the type of the object referred by the capability.

#### See also

[L4::Cap](#) for typed capabilities.

Definition at line 25 of file [capability.h](#).



## 15.80.2 Member Enumeration Documentation

### 15.80.2.1 Cap\_type

enum [L4::Cap\\_base::Cap\\_type](#)

Invalid capability type.

#### Enumerator

Invalid	Invalid capability selector.
---------	------------------------------

Definition at line [40](#) of file [capability.h](#).

### 15.80.2.2 No\_init\_type

enum [L4::Cap\\_base::No\\_init\\_type](#)

Special value for uninitialized capability objects.

#### Enumerator

No_init	Special value for constructing uninitialized <a href="#">Cap</a> objects.
---------	---

Definition at line [29](#) of file [capability.h](#).

## 15.80.3 Constructor & Destructor Documentation

### 15.80.3.1 Cap\_base() [1/2]

```
L4::Cap_base::Cap_base (
    l4\_cap\_idx\_t c) [inline], [explicit], [protected], [noexcept]
```

Generate a capability from its C representation.

#### Parameters


<i>c</i>	The C capability
----------	------------------

Definition at line [149](#) of file [capability.h](#).

References [\\_c](#).

Referenced by [L4::Cap< A >::Cap\(\)](#), [L4::Cap< A >::Cap\(\)](#), [L4::Cap< A >::Cap\(\)](#), [L4::Cap< A >::Cap\(\)](#), [copy\(\)](#), [move\(\)](#), [operator!=\(\)](#), and [operator==\(\)](#).

Here is the caller graph for this function:



### 15.80.3.2 Cap\_base() [2/2]

```
L4::Cap_base::Cap_base (
    l4\_default\_caps\_t cap) [inline], [explicit], [protected], [noexcept]
```

Initialize capability with one of the default capabilities.


#### Parameters

<i>cap</i>	Capability.
------------	-------------

Definition at line [160](#) of file [capability.h](#).

References [\\_c](#), and [cap\(\)](#).

Here is the call graph for this function:



## 15.80.4 Member Function Documentation

### 15.80.4.1 cap()

```
l4_cap_idx_t L4::Cap_base::cap () const [inline], [noexcept]
```

Return capability selector.

#### Returns


Capability selector.

Definition at line 49 of file [capability.h](#).

References [\\_c](#).

Referenced by [L4::Thread\\_group::add\(\)](#), [L4Re::Util::Br\\_manager::alloc\\_buffer\\_demand\(\)](#), [L4vbus::Vbus::assign\\_dma\\_domain\(\)](#), [L4vbus::Vbus::assign\\_dma\\_domain\(\)](#), [L4::lcu::bind\(\)](#), [L4::Rcv\\_endpoint::bind\\_snd\\_destination\(\)](#), [L4::Irq::bind\\_vcpu\(\)](#), [L4::Cap< A >::Cap\(\)](#), [L4::Cap< A >::Cap\(\)](#), [Cap\\_base\(\)](#), [Cap\\_base\(\)](#), [L4::Task::cap\\_equal\(\)](#), [L4::Task::cap\\_valid\(\)](#), [L4Re::Smart\\_count\\_cap< Unmap\\_flags >::copy\(\)](#), [L4Re::Util::Smart\\_count\\_cap< Unmap\\_flags >::copy\(\)](#), [L4::Factory::create\\_factory\(\)](#), [L4::Factory::create\\_gate\(\)](#), [L4::Factory::create\\_task\(\)](#), [L4::Factory::create\\_thread\\_group\(\)](#), [L4::Task::delete\\_obj\(\)](#), [L4Re::Util::Smart\\_cap\\_auto< Unmap\\_flags >::free\(\)](#), [L4::Task::map\(\)](#), [L4Re::Util::Event\\_buffer\\_consumer\\_t< T >::map\(\)](#), [L4Re::Util::Br\\_manager::realloc\\_rcv\\_cap\(\)](#), [L4::Thread::register\\_del\\_irq\(\)](#), [L4::Thread::register\\_doorbell\\_irq\(\)](#), [L4::Task::release\\_cap\(\)](#), [L4::Thread\\_group::remove\(\)](#), [L4::lcu::unbind\(\)](#), and [L4vbus::lcu::vicu\(\)](#).

Here is the caller graph for this function:



### 15.80.4.2 copy()

```
void L4::Cap_base::copy (
    Cap_base const & src) const [inline], [protected]
```

Copy a capability.

**Parameters**

<i>src</i>	the source capability.
------------	------------------------


After this operation this capability refers to the same object as `src`.

Definition at line 192 of file `capability.h`.

References `Cap_base()`, `fpage()`, `is_valid()`, `L4_BASE_TASK_CAP`, `L4_CAP_FPAGE_RWSD`, `L4_FPAGE_C_OBJ_RIGHTS`, `l4_task_map()`, and `snd_base()`.

Referenced by `L4::Cap< A >::copy()`.

Here is the call graph for this function:



Here is the caller graph for this function:

**15.80.4.3 fpage()**

```
l4_fpage_t L4::Cap_base::fpage (
    unsigned rights = L4_CAP_FPAGE_RWS) const [inline], [noexcept]
```

Return flexpage for the capability.

**Parameters**

<i>rights</i>	Rights, defaults to 'rws'
---------------	---------------------------

**Returns**

flexpage

Definition at line 74 of file [capability.h](#).


References [\\_c](#), [L4\\_CAP\\_FPAGE\\_RWS](#), and [l4\\_obj\\_fpage\(\)](#).

Referenced by [copy\(\)](#), [move\(\)](#), and [L4Re::Util::Object\\_registry::unregister\\_obj\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:

**15.80.4.4 is\_valid()**

```
bool L4::Cap_base::is_valid () const [inline], [noexcept]
```

Test whether the capability is a valid capability index (i.e., not `L4_INVALID_CAP`).

**Returns**

True if capability is not invalid, false if invalid

**Examples**


[examples/libs/l4re/c++/mem\\_alloc/ma+rm.cc](#), and [examples/libs/l4re/c++/shared\\_ds/ds\\_clnt.cc](#).

Definition at line 57 of file [capability.h](#).

References [\\_c](#).

Referenced by [copy\(\)](#), [L4Re::Smart\\_count\\_cap< Unmap\\_flags >::copy\(\)](#), [L4Re::Util::Smart\\_cap\\_auto< Unmap\\_flags >::free\(\)](#), [L4Re::Util::Event\\_t< Default\\_event\\_payload >::init\(\)](#), [L4Re::Util::Event\\_t< Default\\_event\\_payload >::init\\_poll\(\)](#), [L4Re::Util::Smart\\_cap\\_auto< Unmap\\_flags >::invalidate\(\)](#), [move\(\)](#), [L4Re::Util::Object\\_registry::unregister\\_obj\(\)](#), [validate\(\)](#), and [validate\(\)](#).

Here is the caller graph for this function:



#### 15.80.4.5 move()

```
void L4::Cap_base::move (
    Cap_base const & src) const [inline], [protected]
```

Replace this capability with the contents of `src`.

#### Parameters

<code>src</code>	the source capability.
------------------	------------------------


After the operation this capability refers to the object formerly referred to by the source capability `src`, and the source capability no longer refers to an object.

Definition at line 176 of file [capability.h](#).

References [Cap\\_base\(\)](#), [fpage\(\)](#), [is\\_valid\(\)](#), [L4\\_BASE\\_TASK\\_CAP](#), [L4\\_CAP\\_FPAGE\\_RWSD](#), [L4\\_FPAGE\\_C\\_OBJ\\_RIGHTS](#), [L4\\_MAP\\_ITEM\\_GRANT](#), [l4\\_task\\_map\(\)](#), and [snd\\_base\(\)](#).

Referenced by [L4::Cap< A >::move\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



#### 15.80.4.6 `snd_base()`

```

l4_umword_t L4::Cap_base::snd_base (
    unsigned grant = L4_MAP_ITEM_MAP,
    l4_cap_idx_t base = L4_INVALID_CAP) const [inline], [noexcept]
  
```

Return send base.

#### Parameters

<i>grant</i>	Indicates if object shall be granted. Allowed values: <a href="#">L4_MAP_ITEM_MAP</a> , <a href="#">L4_MAP_ITEM_GRANT</a> .
<i>base</i>	Base capability (first in a bundle of aligned capabilities)



**Returns**


Map object.

Definition at line 86 of file [capability.h](#).


References [\\_c](#), [L4\\_INVALID\\_CAP](#), [L4\\_MAP\\_ITEM\\_MAP](#), and [l4\\_map\\_obj\\_control\(\)](#).

Referenced by [copy\(\)](#), and [move\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:

**15.80.4.7 validate() [1/2]**

```

l4_msgtag_t L4::Cap_base::validate (
    Cap< Task > task,
    l4_utcb_t * u = l4_utcb()) const [inline], [noexcept]
  
```

Check whether a capability is present (refers to an object).

**Parameters**

<i>task</i>	<a href="#">Task</a> to check the capability in.
<i>u</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. See <a href="#">l4_utcb</a> .

**Return values**


<i>l4_msgtag_t::label()</i> > 0	Capability is present (refers to an object).
<i>l4_msgtag_t::label()</i> == 0	No capability present (void object or invalid capability slot).

A capability is considered present when it refers to an existing kernel object.

Definition at line 74 of file [capability](#).

References [\\_c](#), [is\\_valid\(\)](#), and [l4\\_msgtag\(\)](#).

Here is the call graph for this function:



#### 15.80.4.8 validate() [2/2]

```
l4_msgtag_t L4::Cap_base::validate (
    l4_utcb_t * u = l4_utcb()) const [inline], [noexcept]
```

Check whether a capability is present (refers to an object).

##### Parameters

<i>u</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. See <a href="#">l4_utcb</a> .
----------	--

##### Return values


<i>l4_msgtag_t::label()</i> > 0	Capability is present (refers to an object).
<i>l4_msgtag_t::label()</i> == 0	No capability present (void object or invalid capability slot).

A capability is considered present when it refers to an existing kernel object.

Definition at line 81 of file [capability](#).

References [\\_c](#), [is\\_valid\(\)](#), [L4\\_BASE\\_TASK\\_CAP](#), and [l4\\_msgtag\(\)](#).

Here is the call graph for this function:



The documentation for this class was generated from the following files:


- l4/sys/cxx/capability.h
- l4/sys/[capability](#)

## 15.81 L4::Com\_error Class Reference


Error conditions during IPC.

```
#include <l4/cxx/exceptions>
```

Inheritance diagram for L4::Com\_error:



Collaboration diagram for L4::Com\_error:



### Public Member Functions

- [Com\\_error](#) (long err) noexcept  
Create a [Com\\_error](#) for the given [L4](#) IPC error code.

### Public Member Functions inherited from [L4::Runtime\\_error](#)

- [Runtime\\_error](#) (long [err\\_no](#), char const \*extra=0) noexcept

Create a new [Runtime\\_error](#).

- char const \* **str** () const noexcept override  
*Return a human readable string for the exception.*
- char const \* **extra\_str** () const  
*Get the description text for this runtime error.*
- long **err\_no** () const noexcept  
*Get the error value for this runtime error.*

### Public Member Functions inherited from [L4::Base\\_exception](#)

- virtual ~**Base\_exception** () noexcept  
*Destruction.*

### Public Member Functions inherited from [L4::Exception\\_tracer](#)

- void const \*const \* **pc\_array** () const noexcept  
*Get the array containing the call trace.*
- int **frame\_count** () const noexcept  
*Get the number of entries that are valid in the call trace.*

### Additional Inherited Members

### Protected Member Functions inherited from [L4::Base\\_exception](#)

- **Base\_exception** () noexcept  
*Create a base exception.*

### Protected Member Functions inherited from [L4::Exception\\_tracer](#)

- **Exception\_tracer** () noexcept  
*Create a back trace.*

## 15.81.1 Detailed Description

Error conditions during IPC.

This exception encapsulates all IPC error conditions of [L4](#) IPC.

Definition at line 263 of file [exceptions](#).

## 15.81.2 Constructor & Destructor Documentation

### 15.81.2.1 Com\_error()

```
L4::Com_error::Com_error (  
    long err) [inline], [explicit], [noexcept]
```

Create a [Com\\_error](#) for the given [L4](#) IPC error code.

#### Parameters

<i>err</i>	The <a href="#">L4</a> IPC error code (l4_ipc... return value).
------------	---

Definition at line [270](#) of file [exceptions](#).

The documentation for this class was generated from the following file:


- [l4/cxx/exceptions](#)

## 15.82 L4::Debugger Class Reference


C++ kernel debugger API.

```
#include <debugger>
```

Inheritance diagram for L4::Debugger:



Collaboration diagram for L4::Debugger:



## Public Member Functions

- `l4_msgtag_t set_object_name` (const char \*name, `l4_utcb_t` \*utcb=`l4_utcb()`) noexcept  
Set the name of a kernel object.
- unsigned long `global_id` (`l4_utcb_t` \*utcb=`l4_utcb()`) noexcept  
Get the globally unique ID of the object behind a capability.
- unsigned long `kobj_to_id` (`l4_addr_t` kobjp, `l4_utcb_t` \*utcb=`l4_utcb()`) noexcept  
Get the globally unique ID of the object behind the kobject pointer.



- [l4\\_ret\\_t query\\_log\\_typeid](#) (const char \*name, unsigned idx, [l4\\_utcb\\_t](#) \*utcb=[l4\\_utcb\(\)](#)) noexcept  
*Query the log-id for a log type.*
- [l4\\_ret\\_t query\\_log\\_name](#) (unsigned idx, char \*name, unsigned namelen, char \*shortname, unsigned short-namelen, [l4\\_utcb\\_t](#) \*utcb=[l4\\_utcb\(\)](#)) noexcept  
*Query the name of a log type given the ID.*
- [l4\\_msgtag\\_t switch\\_log](#) (const char \*name, unsigned on\_off, [l4\\_utcb\\_t](#) \*utcb=[l4\\_utcb\(\)](#)) noexcept  
*Set or unset log.*
- [l4\\_msgtag\\_t query\\_object\\_name](#) (unsigned id, char \*name, unsigned size, [l4\\_utcb\\_t](#) \*utcb=[l4\\_utcb\(\)](#)) noexcept  
*Get name of object with Id id.*
- [l4\\_msgtag\\_t get\\_object\\_name](#) (char \*name, unsigned size, [l4\\_utcb\\_t](#) \*utcb=[l4\\_utcb\(\)](#)) noexcept  
*Get name of object.*
- [l4\\_msgtag\\_t add\\_image\\_info](#) ([l4\\_addr\\_t](#) base, const char \*name, [l4\\_utcb\\_t](#) \*utcb=[l4\\_utcb\(\)](#)) noexcept  
*Add loaded image information for a task.*

## Public Member Functions inherited from [L4::Kobject](#)

- [l4\\_msgtag\\_t dec\\_refcnt](#) ([l4\\_mword\\_t](#) diff, [l4\\_utcb\\_t](#) \*utcb=[l4\\_utcb\(\)](#))  
*Decrement the in kernel reference counter for the object.*

## Additional Inherited Members

## Protected Types inherited from

[L4::Kobject\\_t](#) < [Debugger](#), [Kobject](#), [L4\\_PROTO\\_DEBUGGER](#) >

- typedef [Debugger](#) **Class**  
*The target interface type (inheriting from [Kobject\\_t](#)).*
- typedef Typeid::Iface< [PROTO](#), [Debugger](#) > **\_\_Iface**  
*The interface description for the derived class.*
- typedef Typeid::Merge\_list< Typeid::Iface\_list< **\_\_Iface** >, typename [Kobject](#)::\_\_Iface\_list > **\_\_Iface\_list**  
*The list of all RPC interfaces provided directly or through inheritance.*

## Protected Member Functions inherited from

[L4::Kobject\\_t](#) < [Debugger](#), [Kobject](#), [L4\\_PROTO\\_DEBUGGER](#) >

- [L4::Cap](#) < **Class** > **c** () const noexcept  
*Get the capability to ourselves.*

## Protected Member Functions inherited from [L4::Kobject](#)

- [l4\\_cap\\_idx\\_t cap](#) () const noexcept  
*Return capability selector.*

## Static Protected Member Functions inherited from

[L4::Kobject\\_t](#) < [Debugger](#), [Kobject](#), [L4\\_PROTO\\_DEBUGGER](#) >

- static void **\_\_check\_protocols** () noexcept  
*Helper to check for protocol conflicts.*

### 15.82.1 Detailed Description

C++ kernel debugger API.

#### Attention

This API is subject to change! Do not rely on it in production code.

This API is to be used for debugging exclusively.

This is the API for accessing kernel-debugger functionality from user-level programs. Specifically, it provides functionality to enrich the kernel debugger with insights into the program. The purpose is to facilitate debugging with the kernel debugger. For instance, a developer might choose to name the threads of her program so that she can find them in the kernel debugger thread list.

This API interacts with a kernel object that interfaces with the kernel debugger, the jdb-kernel object. The jdb-kernel object is fix and only available when the kernel debugger is built into the microkernel. The developer needs to pass the capability through to her program.

#### Include File

```
#include <l4/sys/debugger>
```

Definition at line 42 of file [debugger](#).

### 15.82.2 Member Function Documentation

#### 15.82.2.1 add\_image\_info()

```
l4_msgtag_t L4::Debugger::add_image_info (
    l4_addr_t base,
    const char * name,
    l4_utcb_t * utcb = l4_utcb()) [inline], [noexcept]
```

Add loaded image information for a task.

#### Parameters

<i>base</i>	Image load base address
<i>name</i>	Image name
<i>utcb</i>	The UTCB to use for the operation.


#### Returns

System call return tag.

Definition at line 175 of file [debugger](#).

References [L4::Kobject::cap\(\)](#).

Here is the call graph for this function:



### 15.82.2.2 get\_object\_name()

```
l4_msgtag_t L4::Debugger::get_object_name (
    char * name,
    unsigned size,
    l4_utcb_t * utcb = l4_utcb()) [inline], [noexcept]
```

Get name of object.

#### Parameters

out	<i>name</i>	Buffer to copy the name into. The buffer must be allocated by the caller.
	<i>size</i>	Length of the <i>name</i> buffer.
	<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. See <a href="#">l4_utcb</a> .


#### Returns

Syscall return tag

Definition at line 162 of file [debugger](#).

References [L4::Kobject::cap\(\)](#).

Here is the call graph for this function:



### 15.82.2.3 global\_id()

```
unsigned long L4::Debugger::global_id (
    l4_utcb_t * utcb = l4_utcb()) [inline], [noexcept]
```

Get the globally unique ID of the object behind a capability.

#### Parameters

<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. Defaults to <a href="#">l4_utcb</a> .
-------------	--


#### Return values

$\sim 0UL$	The capability is invalid.
$\geq 0$	The global debugger id.

Definition at line 71 of file [debugger](#).

References [L4::Kobject::cap\(\)](#).

Here is the call graph for this function:



#### 15.82.2.4 kobj\_to\_id()

```

unsigned long L4::Debugger::kobj_to_id (
    l4_addr_t kobjp,
    l4_utcb_t * utcb = l4_utcb()) [inline], [noexcept]
  
```

Get the globally unique ID of the object behind the kobject pointer.

##### Parameters

<i>kobjp</i>	<a href="#">Kobject</a> pointer
<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. See <a href="#">l4_utcb</a> .

##### Return values

$\sim 0UL$	The capability or the <a href="#">Kobject</a> pointer are invalid.
$\geq 0$	The globally unique id.

Definition at line 83 of file [debugger](#).

References [L4::Kobject::cap\(\)](#).

Here is the call graph for this function:



### 15.82.2.5 query\_log\_name()

```
l4_ret_t L4::Debugger::query_log_name (
    unsigned idx,
    char * name,
    unsigned namelen,
    char * shortname,
    unsigned shortnamelen,
    l4_utcb_t * utcb = l4_utcb()) [inline], [noexcept]
```

Query the name of a log type given the ID.

#### Parameters

	<i>idx</i>	ID to query.
out	<i>name</i>	<a href="#">Buffer</a> to copy name to. The buffer must be allocated by the caller.
	<i>namelen</i>	<a href="#">Buffer</a> length of name.
out	<i>shortname</i>	<a href="#">Buffer</a> to copy shortname to. The buffer must be allocated by the caller.
	<i>shortnamelen</i>	<a href="#">Buffer</a> length of shortname.
	<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. See <a href="#">l4_utcb</a> .

#### Return values

0	Success
<0	Error

Definition at line 116 of file [debugger](#).

References [L4::Kobject::cap\(\)](#).

Here is the call graph for this function:



### 15.82.2.6 query\_log\_typeid()

```
l4_ret_t L4::Debugger::query_log_typeid (
    const char * name,
```

```

    unsigned idx,
    l4_utcb_t * utcb = l4_utcb()) [inline], [noexcept]

```

Query the log-id for a log type.

#### Parameters

<i>name</i>	Name to query for.
<i>idx</i>	Idx to start searching, start with 0
<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. See <a href="#">l4_utcb</a> .

#### Return values

$\geq 0$	Id
$< 0$	Error

Definition at line 97 of file [debugger](#).

References [L4::Kobject::cap\(\)](#).

Here is the call graph for this function:



#### 15.82.2.7 query\_object\_name()

```

l4_msgtag_t L4::Debugger::query_object_name (
    unsigned id,
    char * name,
    unsigned size,
    l4_utcb_t * utcb = l4_utcb()) [inline], [noexcept]

```

Get name of object with Id *id*.

#### Parameters

	<i>id</i>	Id of the object whose name is asked.
out	<i>name</i>	<a href="#">Buffer</a> to copy the name into. The buffer must be allocated by the caller.
	<i>size</i>	Length of the <i>name</i> buffer.

	<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. See <a href="#">l4_utcb</a> .
--	-------------	--

**Returns**

Syscall return tag

Definition at line 148 of file [debugger](#).

References [L4::Kobject::cap\(\)](#).

Here is the call graph for this function:

**15.82.2.8 set\_object\_name()**

```

l4_msgtag_t L4::Debugger::set_object_name (
    const char * name,
    l4_utcb_t * utcb = l4_utcb()) [inline], [noexcept]
  
```

Set the name of a kernel object.

**Parameters**

<i>name</i>	Name
<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. Defaults to <a href="#">l4_utcb</a> .


**Returns**

System call return tag.

Definition at line 59 of file [debugger](#).

References [L4::Kobject::cap\(\)](#).

Here is the call graph for this function:



### 15.82.2.9 switch\_log()

```
l4_msgtag_t L4::Debugger::switch_log (
    const char * name,
    unsigned on_off,
    l4_utcb_t * utcb = l4_utcb()) [inline], [noexcept]
```

Set or unset log.

#### Parameters

<i>name</i>	Name of the log type.
<i>on_off</i>	1: turn log on, 0: turn log off
<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. See <a href="#">l4_utcb</a> .

#### Returns

Syscall return tag

Definition at line [133](#) of file [debugger](#).

References [L4::Kobject::cap\(\)](#).

Here is the call graph for this function:



The documentation for this class was generated from the following file:

- [l4/sys/debugger](#)


## 15.83 L4::Element\_already\_exists Class Reference

[Exception](#) for duplicate element insertions.


```
#include <l4/cxx/exceptions>
```



Inheritance diagram for L4::Element\_already\_exists:



Collaboration diagram for L4::Element\_already\_exists:



#### Additional Inherited Members

#### Public Member Functions inherited from [L4::Runtime\\_error](#)

- [Runtime\\_error](#) (long `err_no`, char const \*extra=0) noexcept  
Create a new [Runtime\\_error](#).
- char const \* **str** () const noexcept override

*Return a human readable string for the exception.*

- `char const * extra\_str () const`

*Get the description text for this runtime error.*

- `long err\_no () const noexcept`

*Get the error value for this runtime error.*

### Public Member Functions inherited from [L4::Base\\_exception](#)

- `virtual ~Base_exception () noexcept`

*Destruction.*

### Public Member Functions inherited from [L4::Exception\\_tracer](#)

- `void const *const * pc_array () const noexcept`

*Get the array containing the call trace.*

- `int frame_count () const noexcept`

*Get the number of entries that are valid in the call trace.*

### Protected Member Functions inherited from [L4::Base\\_exception](#)

- `Base_exception () noexcept`

*Create a base exception.*

### Protected Member Functions inherited from [L4::Exception\\_tracer](#)

- `Exception_tracer () noexcept`

*Create a back trace.*

## 15.83.1 Detailed Description

[Exception](#) for duplicate element insertions.

Definition at line 192 of file [exceptions](#).

The documentation for this class was generated from the following file:


- `I4/cxx/exceptions`

## 15.84 L4::Element\_not\_found Class Reference


[Exception](#) for a failed lookup (element not found).

```
#include <l4/cxx/exceptions>
```

Inheritance diagram for L4::Element\_not\_found:



Collaboration diagram for L4::Element\_not\_found:



### Additional Inherited Members

### Public Member Functions inherited from [L4::Runtime\\_error](#)

- [Runtime\\_error](#) (long [err\\_no](#), char const \*extra=0) noexcept  
Create a new [Runtime\\_error](#).
- char const \* **str** () const noexcept override  
Return a human readable string for the exception.

- `char const * extra\_str () const`  
*Get the description text for this runtime error.*
- `long err\_no () const noexcept`  
*Get the error value for this runtime error.*

### Public Member Functions inherited from [L4::Base\\_exception](#)

- `virtual ~Base_exception () noexcept`  
*Destruction.*

### Public Member Functions inherited from [L4::Exception\\_tracer](#)

- `void const *const * pc_array () const noexcept`  
*Get the array containing the call trace.*
- `int frame_count () const noexcept`  
*Get the number of entries that are valid in the call trace.*

### Protected Member Functions inherited from [L4::Base\\_exception](#)

- `Base_exception () noexcept`  
*Create a base exception.*

### Protected Member Functions inherited from [L4::Exception\\_tracer](#)

- `Exception_tracer () noexcept`  
*Create a back trace.*

## 15.84.1 Detailed Description

[Exception](#) for a failed lookup (element not found).

Definition at line 220 of file [exceptions](#).

The documentation for this class was generated from the following file:


- [l4/cxx/exceptions](#)

## 15.85 L4::Epiface Struct Reference


Base class for interface implementations.

```
#include <ipc_epiface>
```

Inheritance diagram for L4::Epiface:



Collaboration diagram for L4::Epiface:



## Public Types

- typedef `ipc_svr::Server_iface` **Server\_iface**  
*Type for abstract server interface.*
- typedef `ipc_svr::Server_iface::Demand` **Demand**  
*Type for server-side receive buffer demand.*

## Public Member Functions

- **Epiface ()**  
*Make a server object.*
- virtual `l4_msgtag_t dispatch (l4_msgtag_t tag, unsigned rights, l4_utcb_t *utcb)=0`  
*The abstract handler for client requests to the object.*
- virtual `Demand get_buffer_demand () const =0`  
*Get the server-side receive buffer demand for this object.*
- virtual `~Epiface ()=0`  
*Destroy the object.*
- Stored\_cap `obj_cap () const`  
*Get the capability to the kernel object belonging to this object.*
- `Server_iface * server_iface () const`  
*Get pointer to server interface at which the object is currently registered.*
- int `set_server (Server_iface *srv, Cap< void > cap, bool managed=false)`  
*Set server registration info for the object.*
- void `set_obj_cap (Cap< void > const &cap)`  
*Deprecated server registration function.*

### 15.85.1 Detailed Description

Base class for interface implementations.

An [Epiface](#) is the base interface of objects registered in the server loop. Incoming IPC gets dispatched to the appropriate [Epiface](#) object where the call is then handled appropriately.

#### Note

[Server](#) loops are allowed to internally keep raw pointers to [Epiface](#) objects for dispatching calls. Instances must therefore never be copied or moved.

Definition at line 145 of file [ipc\\_epiface](#).

### 15.85.2 Member Function Documentation

#### 15.85.2.1 dispatch()

```
virtual l4_msgtag_t L4::Epiface::dispatch (
    l4_msgtag_t tag,
    unsigned rights,
    l4_utcb_t * utcb) [pure virtual]
```

The abstract handler for client requests to the object.

#### Parameters

<i>tag</i>	The message tag for this invocation.
<i>rights</i>	The rights bits in the invoked capability.



<i>utcb</i>	The UTCB used for the invocation.
-------------	-----------------------------------

### Return values


<code>-L4_ENOREPLY</code>	No reply message is send.
<code>&lt;0</code>	Error, reply with error code.
<code>&gt;=0</code>	Success, reply with return value.

This function must be implemented by application specific server objects.

Implemented in [L4::Epiface\\_t< Derived, IFACE, BASE, bool >](#), [L4::Epiface\\_t< Block\\_dev< Ds\\_data >, L4virtio::Device >](#), [L4::Epiface\\_t< Null\\_handler, L4::Kobject >](#), [L4::Epiface\\_t< Stats\\_reader, Virtio\\_net\\_switch::Statistics\\_if >](#), [L4::Epiface\\_t< Switch\\_factory, L4::Factory >](#), [L4::Epiface\\_t< Virtio\\_gpio< Request\\_handler, L4virtio::Device >, L4virtio::Device >](#), [L4::Epiface\\_t< Virtio\\_i2c< Request\\_handler, L4virtio::Device >, L4virtio::Device >](#), [L4::Epiface\\_t< Virtio\\_net, L4virtio::Device >](#), [L4::Epiface\\_t< Virtio\\_rng< Rnd\\_state >, L4virtio::Device >](#), [L4::Epiface\\_t< Virtio\\_spi< Spi\\_request\\_handler, L4virtio::Device >, L4virtio::Device >](#), [L4::Irqep\\_t< Derived, BASE, bool >](#), [L4::Irqep\\_t< Del\\_cap\\_irq >](#), [L4::Irqep\\_t< Host\\_irq >](#), [L4::Irqep\\_t< Irq\\_object >](#), [L4::Irqep\\_t< Kick\\_irq >](#), and [L4::Server\\_object](#).

Referenced by [L4::Basic\\_registry::dispatch\(\)](#).

Here is the caller graph for this function:



### 15.85.2.2 get\_buffer\_demand()

```
virtual Demand L4::Epiface::get_buffer_demand () const [pure virtual]
```

Get the server-side receive buffer demand for this object.

#### Note

This function is usually not implemented directly, but by using [Server\\_object\\_t](#) template with an IPC interface definition.

#### Returns

The needed server-side receive buffers for this object

Implemented in [L4::Epiface\\_t0< RPC\\_IFACE, BASE >](#), [L4::Epiface\\_t0< IFACE, L4::Epiface >](#), [L4::Epiface\\_t0< L4::Factory, L4::Epiface >](#), [L4::Epiface\\_t0< L4::Kobject, L4::Epiface >](#), [L4::Epiface\\_t0< L4virtio::Device, L4::Epiface >](#), [L4::Epiface\\_t0< Virtio\\_net\\_switch::Statistics\\_if, L4::Epiface >](#), [L4::Epiface\\_t0< void, Epiface >](#), [L4::Server\\_object\\_t< IFACE, BASE >](#), [L4::Server\\_object\\_t< IFACE, L4::Server\\_object >](#), and [L4::Server\\_object\\_t< Kobject >](#).

### 15.85.2.3 obj\_cap()

```
Stored_cap L4::Epiface::obj_cap () const [inline]
```

Get the capability to the kernel object belonging to this object.

#### Returns


Capability for the kernel object behind the server.

This is usually either an [lpc\\_gate](#) or an [lrc](#).

Definition at line 206 of file [ipc\\_epiface](#).

Referenced by [L4Re::Util::Object\\_registry::unregister\\_obj\(\)](#).

Here is the caller graph for this function:



### 15.85.2.4 server\_iface()

```
Server_iface * L4::Epiface::server_iface () const [inline]
```

Get pointer to server interface at which the object is currently registered.


#### Returns

Pointer to the server at which the object is currently registered, NULL if the object is not registered at any server.

Definition at line 213 of file [ipc\\_epiface](#).

Referenced by [L4virtio::Svr::Virtio\\_gpio< Request\\_handler, Epiface >::register\\_single\\_driver\\_irq\(\)](#), [L4virtio::Svr::Virtio\\_i2c< Request\\_handler, Epiface >::register\\_single\\_driver\\_irq\(\)](#), [L4virtio::Svr::Virtio\\_rng< Rnd\\_state, Epiface >::register\\_single\\_driver\\_irq\(\)](#), [L4virtio::Svr::Virtio\\_spi< Spi\\_request\\_handler, Epiface >::register\\_single\\_driver\\_irq\(\)](#), and [Virtio\\_net::register\\_single\\_driver\\_irq\(\)](#).

Here is the caller graph for this function:



### 15.85.2.5 set\_server()

```
int L4::Epiface::set_server (
    Server_iface * srv,
    Cap< void > cap,
    bool managed = false) [inline]
```


Set server registration info for the object.

#### Parameters

<i>srv</i>	The server to register at
<i>cap</i>	The capability that connects the object.
<i>managed</i>	Mark the capability as managed or unmanaged. Typical server implementations use this flag to remember whether the capability was internally allocated or not.



Collaboration diagram for L4::Epiface\_t< Derived, IFACE, BASE, bool >:



### Public Member Functions

- `l4_msgtag_t dispatch (l4_msgtag_t tag, unsigned rights, l4_utcb_t *utcb) final`  
*The abstract handler for client requests to the object.*

### Public Member Functions inherited from [L4::Epiface\\_t0< IFACE, L4::Epiface >](#)

- `Type_info::Demand get_buffer_demand () const`

*Get the server-side buffer demand based in IFACE.*

- [Cap](#)< IFACE > [obj\\_cap](#) () const

*Get the (typed) capability to this object.*

## Public Member Functions inherited from [L4::Epiface](#)

- **Epiface** ()

*Make a server object.*

- virtual **~Epiface** ()=0

*Destroy the object.*

- Stored\_cap [obj\\_cap](#) () const

*Get the capability to the kernel object belonging to this object.*

- [Server\\_iface](#) \* [server\\_iface](#) () const

*Get pointer to server interface at which the object is currently registered.*

- int [set\\_server](#) ([Server\\_iface](#) \*srv, [Cap](#)< void > cap, bool managed=false)

*Set server registration info for the object.*

- void **set\_obj\_cap** ([Cap](#)< void > const &cap)

*Deprecated server registration function.*

## Additional Inherited Members

## Public Types inherited from [L4::Epiface\\_t0](#)< IFACE, [L4::Epiface](#) >

- typedef IFACE **Interface**

*Data type of the IPC interface definition.*

## Public Types inherited from [L4::Epiface](#)

- typedef [ipc\\_svr::Server\\_iface](#) **Server\_iface**

*Type for abstract server interface.*

- typedef [ipc\\_svr::Server\\_iface::Demand](#) **Demand**

*Type for server-side receive buffer demand.*

## 15.86.1 Detailed Description

```
template<typename Derived, typename IFACE, typename BASE = L4::Epiface, bool = cxx::is_↵
polymorphic<BASE>::value>
struct L4::Epiface_t< Derived, IFACE, BASE, bool >
```

[Epiface](#) implementation for Kobject-based interface implementations.

### Template Parameters

<i>Derived</i>	Class providing the interface implementations.
<i>BASE</i>	<a href="#">Epiface</a> base class.

### Examples

[examples/clntsrv/src/server.cc](#).

Definition at line 503 of file [ipc\\_epiface](#).

## 15.86.2 Member Function Documentation

### 15.86.2.1 dispatch()

```
template<typename Derived, typename IFACE, typename BASE = L4::Epiface, bool = cxx::is_↵
polymorphic<BASE>::value>
l4_msgtag_t L4::Epiface_t< Derived, IFACE, BASE, bool >::dispatch (
    l4_msgtag_t tag,
    unsigned rights,
    l4_utcb_t * utcb) [inline], [final], [virtual]
```

The abstract handler for client requests to the object.

#### Parameters

<i>tag</i>	The message tag for this invocation.
<i>rights</i>	The rights bits in the invoked capability.
<i>utcb</i>	The UTCB used for the invocation.

#### Return values

<code>-L4_ENOREPLY</code>	No reply message is send.
<code>&lt; 0</code>	Error, reply with error code.
<code>&gt;= 0</code>	Success, reply with return value.

This function must be implemented by application specific server objects.

Implements [L4::Epiface](#).

Definition at line [506](#) of file [ipc\\_epiface](#).

The documentation for this struct was generated from the following file:


- `l4/sys/cxx/ipc_epiface`

## 15.87 L4::Epiface\_t0< RPC\_IFACE, BASE > Struct Template Reference


[Epiface](#) mixin for generic Kobject-based interfaces.

```
#include <ipc_epiface>
```

Inheritance diagram for L4::Epiface\_t0< RPC\_IFACE, BASE >:



Collaboration diagram for L4::Epiface\_t0< RPC\_IFACE, BASE >:





## Public Types

- typedef `RPC_IFACE` **Interface**  
*Data type of the IPC interface definition.*

## Public Types inherited from [L4::Epiface](#)

- typedef `lpc_svr::Server_iface` **Server\_iface**  
*Type for abstract server interface.*
- typedef `lpc_svr::Server_iface::Demand` **Demand**  
*Type for server-side receive buffer demand.*

## Public Member Functions

- `Type_info::Demand` **get\_buffer\_demand** () const  
*Get the server-side buffer demand based in IFACE.*
- `Cap< RPC_IFACE >` **obj\_cap** () const  
*Get the (typed) capability to this object.*

## Public Member Functions inherited from [L4::Epiface](#)

- **Epiface** ()  
*Make a server object.*
- virtual `l4_msgtag_t` **dispatch** (`l4_msgtag_t` tag, unsigned rights, `l4_utcb_t` \*utcb)=0  
*The abstract handler for client requests to the object.*
- virtual `~Epiface` ()=0  
*Destroy the object.*
- Stored\_cap `obj_cap` () const  
*Get the capability to the kernel object belonging to this object.*
- `Server_iface *` **server\_iface** () const  
*Get pointer to server interface at which the object is currently registered.*
- int **set\_server** (`Server_iface *`srv, `Cap< void >` cap, bool managed=false)  
*Set server registration info for the object.*
- void **set\_obj\_cap** (`Cap< void >` const &cap)  
*Deprecated server registration function.*

### 15.87.1 Detailed Description

```
template<typename RPC_IFACE, typename BASE = Epiface>
struct L4::Epiface_t0< RPC_IFACE, BASE >
```

[Epiface](#) mixin for generic Kobject-based interfaces.

#### Template Parameters

<code>RPC_IFACE</code>	Data type of the IPC interface definition.
------------------------	--

<i>BASE</i>	Base <a href="#">Epiface</a> class.
-------------	-------------------------------------

Definition at line 256 of file [ipc\\_epiface](#).

## 15.87.2 Member Function Documentation

### 15.87.2.1 `obj_cap()`

```
template<typename RPC_IFACE, typename BASE = Epiface>
Cap< RPC_IFACE > L4::Epiface_t0< RPC_IFACE, BASE >::obj_cap () const [inline]
```

Get the (typed) capability to this object.


#### Returns

Capability for the kernel object behind the server.

Definition at line 269 of file [ipc\\_epiface](#).

References [L4::cap\\_cast\(\)](#).

Here is the call graph for this function:



The documentation for this struct was generated from the following file:


- `l4/sys/cxx/ipc_epiface`

## 15.88 L4::Exception Class Reference

[Exception](#) interface.

```
#include <exception>
```

Collaboration diagram for `L4::Exception`:



## Public Member Functions

- [l4\\_msgtag\\_t exception](#) ([L4::lpc::In\\_out](#)< [l4\\_exc\\_regs\\_t](#) \* > *regs*, [L4::lpc::Rcv\\_fpage](#) *rwin*, [L4::lpc::Opt](#)< [L4::lpc::Snd\\_fpage](#) & > *fp*)  
*Exception call.*

### 15.88.1 Detailed Description

[Exception](#) interface.

This class defines the interface for handling exception IPC. When an exception occurs during program execution, for example due to a division by zero, the kernel will synthesise an exception IPC and send it to the thread's exception handler, who can then handle it.

The exception handler is set with the [L4::Thread::control](#) interface.

Definition at line 31 of file [exception](#).

### 15.88.2 Member Function Documentation

#### 15.88.2.1 exception()

```
l4\_msgtag\_t L4::Exception::exception (
    L4::Ipc::In\_out< l4\_exc\_regs\_t * > regs,
    L4::Ipc::Rcv\_fpage rwin,
    L4::Ipc::Opt< L4::Ipc::Snd\_fpage & > fp)
```

[Exception](#) call.

#### Parameters

	<i>regs</i>	Register state of the faulting thread.
	<i>rwin</i>	Receive window in the address space.
out	<i>fp</i>	Optional flexpage to resolve the exception.

#### Returns

Message tag containing error code.

The documentation for this class was generated from the following file:


- [l4/sys/exception](#)

## 15.89 L4::Exception\_tracer Class Reference


Back-trace support for exceptions.

```
#include <l4/cxx/exceptions>
```

Inheritance diagram for L4::Exception\_tracer:



Collaboration diagram for L4::Exception\_tracer:



### Public Member Functions

- void const \*const \* **pc\_array** () const noexcept  
*Get the array containing the call trace.*
- int **frame\_count** () const noexcept  
*Get the number of entries that are valid in the call trace.*

### Protected Member Functions

- **Exception\_tracer** () noexcept  
*Create a back trace.*

## 15.89.1 Detailed Description

Back-trace support for exceptions.

This class holds an array of at most [L4\\_CXX\\_EXCEPTION\\_BACKTRACE](#) instruction pointers containing the call trace at the instant when an exception was thrown.

Definition at line 51 of file [exceptions](#).

The documentation for this class was generated from the following file:


- [l4/cxx/exceptions](#)

## 15.90 L4::Factory Class Reference


C++ Factory interface, see [Factory](#) for the C interface.

```
#include <factory>
```

Inheritance diagram for L4::Factory:



Collaboration diagram for L4::Factory:



## Data Structures

- struct [Nil](#)  
*Special type to add a void argument into the factory create stream.*
- struct [Lstr](#)  
*Special type to add a pascal string into the factory create stream.*
- class [S](#)  
*Stream class for the [create\(\)](#) argument stream.*

## Public Member Functions

- **S create** (**Cap**< void > target, long obj, **l4\_utcb\_t** \*utcb=**l4\_utcb**()) noexcept  
*Generic create call to the factory.*
- template<typename OBJ>  
**S create** (**Cap**< OBJ > target, **l4\_utcb\_t** \*utcb=**l4\_utcb**()) noexcept  
*Create call for typed capabilities.*
- **l4\_msgtag\_t create\_task** (**Cap**< **Task** > const &target\_cap, **l4\_fpage\_t** \*utcb\_area, **l4\_utcb\_t** \*utcb=**l4\_utcb**()) noexcept  
*Create a new task.*
- **l4\_msgtag\_t create\_factory** (**Cap**< **Factory** > const &target\_cap, unsigned long limit, **l4\_utcb\_t** \*utcb=**l4\_utcb**()) noexcept  
*Create a new factory.*
- **l4\_msgtag\_t create\_gate** (**Cap**< void > const &target\_cap, **Cap**< **Snd\_destination** > const &snd\_dst\_cap, **l4\_umword\_t** label, **l4\_utcb\_t** \*utcb=**l4\_utcb**()) noexcept  
*Create a new IPC gate, optionally bound to a send destination (a thread or thread group).*
- **l4\_msgtag\_t create\_thread\_group** (**Cap**< **Thread\_group** > const &target\_cap, unsigned policy, **l4\_utcb\_t** \*utcb=**l4\_utcb**()) noexcept  
*Create a new thread group.*

## Public Member Functions inherited from **L4::Kobject**

- **l4\_msgtag\_t dec\_refcnt** (**l4\_mword\_t** diff, **l4\_utcb\_t** \*utcb=**l4\_utcb**())  
*Decrement the in kernel reference counter for the object.*

## Additional Inherited Members

## Protected Types inherited from **L4::Kobject\_t**< **Factory**, **Kobject**, **L4\_PROTO\_FACTORY** >

- typedef **Factory Class**  
*The target interface type (inheriting from **Kobject\_t**).*
- typedef Typeid::Iface< **PROTO**, **Factory** > **\_\_Iface**  
*The interface description for the derived class.*
- typedef Typeid::Merge\_list< Typeid::Iface\_list< **\_\_Iface** >, typename **Kobject**::\_\_Iface\_list > **\_\_Iface\_list**  
*The list of all RPC interfaces provided directly or through inheritance.*

## Protected Member Functions inherited from **L4::Kobject\_t**< **Factory**, **Kobject**, **L4\_PROTO\_FACTORY** >

- **L4::Cap**< **Class** > **c** () const noexcept  
*Get the capability to ourselves.*

## Protected Member Functions inherited from **L4::Kobject**

- **l4\_cap\_idx\_t cap** () const noexcept  
*Return capability selector.*



## Static Protected Member Functions inherited from [L4::Kobject\\_t< Factory, Kobject, L4\\_PROTO\\_FACTORY >](#)

- static void `__check_protocols__()` noexcept  
*Helper to check for protocol conflicts.*

### 15.90.1 Detailed Description

C++ Factory interface, see [Factory](#) for the C interface.

Factories provide an interface to create objects which are accessed via capabilities.

For additional information about which objects can be created via this interface, see server-specific information in [Kernel Factory](#) and [L4Re Servers](#).

#### Include File

```
#include <l4/sys/factory>
```

For the C interface refer to [Factory](#).

Definition at line 38 of file [factory](#).

### 15.90.2 Member Function Documentation

#### 15.90.2.1 `create()` [1/2]

```
template<typename OBJ>
S L4::Factory::create (
    Cap< OBJ > target,
    l4_utcb_t * utcb = l4_utcb()) [inline], [noexcept]
```

Create call for typed capabilities.

#### Template Parameters

<i>OBJ</i>	Capability type of the object to be created.
------------	--

#### Parameters

out	<i>target</i>	Capability of type OBJ.
	<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. Defaults to <a href="#">l4_utcb</a> .

**Returns**

A create stream that allows additional arguments to be passed to the `create()` call via the left-shift (`<<`) operator (see [S::operator <<](#)).

This method does not directly invoke the factory. The factory is invoked when the create stream returned by this method is converted to an [l4\\_msgtag\\_t](#) (see [S::operator l4\\_msgtag\\_t\(\)](#)), or otherwise when the stream goes out of scope (not recommended; see [S::~~S\(\)](#)).

**Precondition**

The invoked [Factory](#) capability must have the permission [L4\\_CAP\\_FPAGE\\_S](#), otherwise the later factory IPC will fail with [L4\\_EPERM](#) (see [S::operator l4\\_msgtag\\_t\(\)](#)).

**Note**

The create stream uses the UTCB to store parameters for the service call. During the lifetime of a create stream or, until it is converted to an [l4\\_msgtag\\_t](#), other UTCB-using operations must not be used.

**Usage:**

```
L4::Cap<L4Re::Dataspace> ds = L4Re::Util::cap_alloc.alloc<L4Re::Dataspace>();
factory->create(ds) << l4_mword_t(size_in_bytes);
```

Definition at line 329 of file [factory](#).

References [L4::Kobject::cap\(\)](#).

Here is the call graph for this function:

**15.90.2.2 create() [2/2]**

```
S L4::Factory::create (
    Cap< void > target,
    long obj,
    l4_utcb_t * utcb = l4_utcb()) [inline], [noexcept]
```

Generic create call to the factory.

**Parameters**

out	<i>target</i>	Capability selector for the new object. The caller must allocate the capability slot. The kernel stores the new objects's capability into this slot.
-----	---------------	--

<i>obj</i>	The protocol ID that specifies which kind of object shall be created.
<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. Defaults to <a href="#">l4_utcb</a> .

### Returns

A create stream that allows additional arguments to be passed to the `create()` call via the left-shift (`<<`) operator (see [S::operator <<](#)).

This method does not directly invoke the factory. The factory is invoked when the create stream returned by this method is converted to an [l4\\_msgtag\\_t](#) (see [S::operator l4\\_msgtag\\_t\(\)](#)), or otherwise when the stream goes out of scope (not recommended; see [S::~S\(\)](#)).

### Precondition

The invoked [Factory](#) capability must have the permission [L4\\_CAP\\_FPAGE\\_S](#), otherwise the later factory IPC will fail with [L4\\_EPERM](#) (see [S::operator l4\\_msgtag\\_t\(\)](#)).

### Note

The create stream uses the UTCB to store parameters for the service call. During the lifetime of a create stream or, until it is converted to an [l4\\_msgtag\\_t](#), other UTCB-using operations must not be used.

### See also

[create\(Cap<OBJ>, l4\\_utcb\\_t \\*\)](#)

Definition at line 292 of file [factory](#).

References [L4::Kobject::cap\(\)](#).

Here is the call graph for this function:



### 15.90.2.3 create\_factory()

```
l4_msgtag_t L4::Factory::create_factory (
    Cap< Factory > const & target_cap,
    unsigned long limit,
    l4_utcb_t * utcb = l4_utcb()) [inline], [noexcept]
```

Create a new factory.

#### Parameters

out	<i>target_cap</i>	The kernel stores the new factory's capability into this slot.
	<i>limit</i>	Limit for the new factory in bytes.
	<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. Defaults to <a href="#">l4_utcb</a> .

#### Returns

Syscall return tag

#### Return values

<i>L4_EOK</i>	No error occurred.
<i>-L4_EPERM</i>	Insufficient permissions; see precondition.
<i>&lt;0</i>	Error code.

#### Precondition

The invoked [Factory](#) capability must have the permission [L4\\_CAP\\_FPAGE\\_S](#).

#### Note


In addition to memory needed for internal data structures, the *limit* (quota) of the new factory is counted towards the quota of the creating factory. The *limit* must be within  $1 \leq \text{limit} \leq 2^{(8 * \text{sizeof}(\text{l4\_umword\_t}) - 1) - 2}$  otherwise the behavior is undefined.

This method is only guaranteed to work with the [Kernel Factory](#). For other services, use the generic [create\(\)](#) method and consult the service documentation for information on the arguments that need to be passed to the create stream.

Definition at line [404](#) of file [factory](#).

References [L4::Cap\\_base::cap\(\)](#), and [L4::Kobject::cap\(\)](#).

Here is the call graph for this function:



### 15.90.2.4 create\_gate()

```
l4_msgtag_t L4::Factory::create_gate (
    Cap< void > const & target_cap,
    Cap< Snd_destination > const & snd_dst_cap,
    l4_umword_t label,
    l4_utcb_t * utcb = l4_utcb()) [inline], [noexcept]
```

Create a new IPC gate, optionally bound to a send destination (a thread or thread group).

#### Parameters

out	<i>target_cap</i>	The kernel stores the new IPC gate's capability into this slot.
	<i>snd_dst_cap</i>	Optional capability selector of a thread or thread group to bind the gate to. Use <a href="#">L4_INVALID_CAP</a> to create an unbound IPC gate.
	<i>label</i>	Optional label of the gate (precisely used if <i>snd_dst_cap</i> is valid). If <i>snd_dst_cap</i> is valid, <i>label</i> must be present.
	<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. Defaults to <a href="#">l4_utcb</a> .

#### Returns

Syscall return tag containing one of the following return codes.

#### Return values

<i>L4_EOK</i>	No error occurred.
<i>-L4_ENOMEM</i>	Out-of-memory during allocation of the <a href="#">lpc_gate</a> object.
<i>-L4_EINVAL</i>	<i>snd_dst_cap</i> is void or points to something that is not a thread or thread group.
<i>-L4_EPERM</i>	Insufficient permissions; see precondition.

#### Precondition

The invoked [Factory](#) capability must have the permission [L4\\_CAP\\_FPAGE\\_S](#). Also *snd\_dst\_cap* (if *valid*) must have the permission [L4\\_CAP\\_FPAGE\\_S](#).

An unbound IPC gate can be bound to a thread or thread group using [L4::lpc\\_gate::bind\\_thread\(\)](#) or [bind\\_snd\\_destination\(\)](#).


#### See also

[L4::lpc\\_gate](#)

Definition at line 440 of file [factory](#).

References [L4::Cap\\_base::cap\(\)](#), and [L4::Kobject::cap\(\)](#).

Here is the call graph for this function:



### 15.90.2.5 create\_task()

```

l4_msgtag_t L4::Factory::create_task (
    Cap< Task > const & target_cap,
    l4_fpage_t * utcb_area,
    l4_utcb_t * utcb = l4_utcb()) [inline], [noexcept]
  
```

Create a new task.

#### Parameters

out	<i>target_cap</i>	The kernel stores the new task's capability into this slot.
in, out	<i>utcb_area</i>	Flexpage that describes an area in the address space of the new task, where the kernel should map the kernel-allocated kernel-user memory to. The kernel uses the kernel-user memory to store UTCBs and vCPU state-save-areas of the new task.

On systems without MMU, the flexpage is adjusted to reflect the actually allocated physical address.

#### Parameters

<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. Defaults to <a href="#">l4_utcb</a> .
-------------	--

#### Returns

Syscall return tag

#### Return values

<i>L4_EOK</i>	No error occurred.
<i>-L4_EPERM</i>	Insufficient permissions; see precondition.
<i>&lt;0</i>	Error code.

**Precondition**

The invoked [Factory](#) capability must have the permission [L4\\_CAP\\_FPAGE\\_S](#).

**Note**

The size of the UTCB area specifies indirectly the number of UTCBs available for this task. Refer to [L4::Task::add\\_ku\\_mem](#) for adding more of this type of memory.


**See also**

[L4::Task](#)

Definition at line 370 of file [factory](#).

References [L4::Cap\\_base::cap\(\)](#), and [L4::Kobject::cap\(\)](#).

Here is the call graph for this function:

**15.90.2.6 create\_thread\_group()**

```

l4_msgtag_t L4::Factory::create_thread_group (
    Cap< Thread_group > const & target_cap,
    unsigned policy,
    l4_utcb_t * utcb = l4_utcb()) [inline], [noexcept]
  
```

Create a new thread group.

An IPC endpoint can be bound to a thread group. When a message arrives at the IPC endpoint, a specific thread of the thread group is selected to actually receive the message. A thread group is a send destination for an IPC endpoint.

**Parameters**

out	<i>target_cap</i>	The kernel stores the new thread group's capability into this slot.
	<i>policy</i>	Policy parameter for the thread group. See <code>L4_thread_group_policy</code> for a list of supported values.

	<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. Defaults to <a href="#">l4_utcb</a> .
--	-------------	--

### Returns

Syscall return tag containing one of the following return codes.


### Return values

<i>L4_EOK</i>	No error occurred.
<i>-L4_ENOMEM</i>	Out-of-memory during allocation of the <a href="#">Thread_group</a> object.
<i>-L4_EINVAL</i>	Invalid policy parameter.
<i>-L4_EPERM</i>	The factory instance requires <a href="#">L4_CAP_FPAGE_S</a> rights on the invoked capability and <a href="#">L4_CAP_FPAGE_S</a> is not present.

Definition at line [475](#) of file [factory](#).

References [L4::Cap\\_base::cap\(\)](#), and [L4::Kobject::cap\(\)](#).

Here is the call graph for this function:



The documentation for this class was generated from the following file:

- [l4/sys/factory](#)

## 15.91 L4::Factory::Lstr Struct Reference

Special type to add a pascal string into the factory create stream.

```
#include <factory>
```



Collaboration diagram for L4::Factory::Lstr:

L4::Factory::Lstr	
+	s
+	len
+	Lstr()

### Public Member Functions

- [Lstr](#) (char const \*[s](#), unsigned [len](#)) noexcept

### Data Fields

- char const \* **s**  
*The character buffer.*
- unsigned **len**  
*The number of characters in the buffer.*

## 15.91.1 Detailed Description

Special type to add a pascal string into the factory create stream.

This encapsulates a string that has an explicit length.

Definition at line [54](#) of file [factory](#).

## 15.91.2 Constructor & Destructor Documentation

### 15.91.2.1 Lstr()

```
L4::Factory::Lstr::Lstr (
    char const * s,
    unsigned len) [inline], [noexcept]
```

### Parameters

<i>s</i>	Pointer to the c-style string.
<i>len</i>	Length in number of characters of the string <i>s</i> .

Definition at line [70](#) of file [factory](#).

References [len](#), and [s](#).

The documentation for this struct was generated from the following file:


- [l4/sys/factory](#)

## 15.92 L4::Factory::Nil Struct Reference

Special type to add a void argument into the factory create stream.

```
#include <factory>
```

Collaboration diagram for L4::Factory::Nil:



### 15.92.1 Detailed Description

Special type to add a void argument into the factory create stream.

Definition at line 47 of file [factory](#).

The documentation for this struct was generated from the following file:


- [l4/sys/factory](#)

## 15.93 L4::Factory::S Class Reference

Stream class for the [create\(\)](#) argument stream.

```
#include <factory>
```

Collaboration diagram for L4::Factory::S:



## Public Member Functions

- `S (S &&o) noexcept`  
*Move constructor.*
- `S (l4_cap_idx_t f, long obj, L4::Cap< void > target, l4_utcb_t *utcb) noexcept`  
*Create a stream for a specific [create\(\)](#) call.*
- `~S () noexcept`  
*Commit the [create\(\)](#) operation if not already done explicitly via [operator l4\\_msgtag\\_t\(\)](#).*
- `operator l4_msgtag_t () noexcept`  
*Explicitly commits the operation and returns the result.*
- `void put (l4_mword_t i) noexcept`  
*Put a single [l4\\_mword\\_t](#) as next argument.*
- `void put (l4_umword_t i) noexcept`  
*Put a single [l4\\_umword\\_t](#) as next argument.*
- `void put (char const *s) &noexcept`  
*Add a zero-terminated string as next argument.*
- `void put (Lstr const &s) &noexcept`  
*Add a pascal string as next argument.*
- `void put (Nil) &noexcept`  
*Add an empty argument.*
- `void put (l4_fpage_t d) &noexcept`  
*Add a flexpage as next argument.*
- `template<typename T>  
S & operator<< (T const &d) &noexcept`

- Add next argument.*
- `template<typename T>`  
`S && operator<< (T const &d) &&noexcept`  
*Add next argument.*

### 15.93.1 Detailed Description

Stream class for the `create()` argument stream.

This stream allows a variable number of arguments to be added to a `create()` call.

Definition at line 79 of file `factory`.

### 15.93.2 Constructor & Destructor Documentation

#### 15.93.2.1 `S()` [1/2]

```
L4::Factory::S::S (
    S && o) [inline], [noexcept]
```

Move constructor.

#### Parameters

<i>o</i>	Instance of <code>S</code> to move.
----------	-------------------------------------

Definition at line 98 of file `factory`.

#### 15.93.2.2 `S()` [2/2]

```
L4::Factory::S::S (
    l4_cap_idx_t f,
    long obj,
    L4::Cap< void > target,
    l4_utcb_t * utcb) [inline], [noexcept]
```

Create a stream for a specific `create()` call.

#### Parameters

	<i>f</i>	The capability for the factory object ( <code>L4::Factory</code> ).
	<i>obj</i>	The protocol ID to describe the type of the object that shall be created.
out	<i>target</i>	The capability selector for the new object. The caller must allocate the capability slot. The kernel stores the new object's capability into this slot.
	<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. See <code>l4_utcb</code> .

#### Precondition

The capability `f` must have the permission `L4_CAP_FPAGE_S`, otherwise the later factory IPC will fail with `L4_EPERM`.

Definition at line 125 of file `factory`.

### 15.93.2.3 ~S()

```
L4::Factory::S::~~S () [inline], [noexcept]
```

Commit the [create\(\)](#) operation if not already done explicitly via [operator l4\\_msgtag\\_t\(\)](#).

#### Warning

If the commit is deferred until destruction, potential errors are silently ignored. It is therefore recommended to commit explicitly via [operator l4\\_msgtag\\_t\(\)](#) and check the return value.

Definition at line 139 of file [factory](#).

## 15.93.3 Member Function Documentation

### 15.93.3.1 operator l4\_msgtag\_t()

```
L4::Factory::S::operator l4_msgtag_t () [inline], [noexcept]
```

Explicitly commits the operation and returns the result.

#### Returns

The result of the [create\(\)](#) operation.

#### Return values

<i>L4_EOK</i>	No error occurred.
<i>-L4_EPERM</i>	Insufficient permissions; see precondition.
<i>&lt;0</i>	Error code.

#### Precondition

The invoked [Factory](#) capability must have the permission [L4\\_CAP\\_FPAGE\\_S](#).

Definition at line 157 of file [factory](#).

**15.93.3.2 operator<<() [1/2]**

```
template<typename T>
S && L4::Factory::S::operator<< (
    T const & d) && [inline], [noexcept]
```

Add next argument.

**Template Parameters**

<i>T</i>	The argument type. Compilation succeeds only if it is a possible argument type for <code>S::put()</code> .
----------	--

**Parameters**

<i>d</i>	The value to add as next argument.
----------	------------------------------------

Definition at line [252](#) of file [factory](#).

References [put\(\)](#).

Here is the call graph for this function:

**15.93.3.3 operator<<() [2/2]**

```
template<typename T>
S & L4::Factory::S::operator<< (
    T const & d) & [inline], [noexcept]
```

Add next argument.

**Template Parameters**

<i>T</i>	The argument type. Compilation succeeds only if it is a possible argument type for <code>S::put()</code> .
----------	--

**Parameters**

<i>d</i>	The value to add as next argument.
----------	------------------------------------

Definition at line 237 of file [factory](#).

References [put\(\)](#).

Here is the call graph for this function:



#### 15.93.3.4 [put\(\)](#) [1/5]

```
void L4::Factory::S::put (
    char const * s) & [inline], [noexcept]
```

Add a zero-terminated string as next argument.

##### Parameters

<i>s</i>	The string to add as next argument.
----------	-------------------------------------

The string will be added with the zero-terminator.

Definition at line 191 of file [factory](#).

#### 15.93.3.5 [put\(\)](#) [2/5]

```
void L4::Factory::S::put (
    l4_fpage_t d) & [inline], [noexcept]
```

Add a flexpage as next argument.

##### Parameters

<i>d</i>	The flexpage to add (there will be no map operation).
----------	---

Definition at line 223 of file [factory](#).

**15.93.3.6 put()** [3/5]

```
void L4::Factory::S::put (
    l4_mword_t i) [inline], [noexcept]
```

Put a single [l4\\_mword\\_t](#) as next argument.


**Parameters**

<i>i</i>	The value to add as next argument.
----------	------------------------------------

Definition at line [169](#) of file [factory](#).

Referenced by [operator<<\(\)](#), and [operator<<\(\)](#).

Here is the caller graph for this function:

**15.93.3.7 put()** [4/5]

```
void L4::Factory::S::put (
    l4_umword_t i) [inline], [noexcept]
```

Put a single [l4\\_umword\\_t](#) as next argument.

**Parameters**

<i>i</i>	The value to add as next argument.
----------	------------------------------------

Definition at line [179](#) of file [factory](#).



### 15.93.3.8 put() [5/5]

```
void L4::Factory::S::put (  
    Lstr const & s) & [inline], [noexcept]
```

Add a pascal string as next argument.

#### Parameters

s	The string to add as next argument.
---	-------------------------------------

The string will be added with the exact length given. It is the responsibility of the caller to make sure that the string is zero- terminated when that is required by the server.

Definition at line [205](#) of file [factory](#).

The documentation for this class was generated from the following file:

- [l4/sys/factory](#)


## 15.94 L4::lcu Class Reference

C++ [lcu](#) interface, see [Interrupt controller](#) for the C interface.

```
#include <irq>
```



Collaboration diagram for L4::Icu:



## Data Structures

- class [Info](#)

*This class encapsulates information about an ICU.*

## Public Member Functions

- [I4\\_msgtag\\_t bind](#) (unsigned irqnum, [L4::Cap< Triggerable >](#) irq, [I4\\_utcb\\_t](#) \*utcb=[I4\\_utcb\(\)](#)) noexcept

*Bind an interrupt line of an interrupt controller to an interrupt object.*

- [l4\\_msgtag\\_t unbind](#) (unsigned irqnum, [L4::Cap< Triggerable >](#) irq, [l4\\_utcb\\_t](#) \*utcb=[l4\\_utcb\(\)](#)) noexcept

*Remove binding of an interrupt line from the interrupt controller object.*

- [l4\\_msgtag\\_t info](#) ([l4\\_icu\\_info\\_t](#) \*info, [l4\\_utcb\\_t](#) \*utcb=[l4\\_utcb\(\)](#)) noexcept

*Get information about the ICU features.*

- [l4\\_msgtag\\_t msi\\_info](#) ([l4\\_umword\\_t](#) irqnum, [l4\\_uint64\\_t](#) source, [l4\\_icu\\_msi\\_info\\_t](#) \*msi\_info)

*Get MSI info about IRQ.*

- [l4\\_msgtag\\_t mask](#) (unsigned irqnum, [l4\\_umword\\_t](#) \*label=0, [l4\\_timeout\\_t](#) to=[L4\\_IPC\\_NEVER](#), [l4\\_utcb\\_t](#) \*utcb=[l4\\_utcb\(\)](#)) noexcept

*Mask an IRQ line.*

- [l4\\_msgtag\\_t set\\_mode](#) (unsigned irqnum, [l4\\_umword\\_t](#) mode, [l4\\_utcb\\_t](#) \*utcb=[l4\\_utcb\(\)](#)) noexcept

*Set interrupt mode.*

## Public Member Functions inherited from [L4::Irq\\_eoi](#)

- [l4\\_msgtag\\_t unmask](#) (unsigned irqnum, [l4\\_umword\\_t](#) \*label=0, [l4\\_timeout\\_t](#) to=[L4\\_IPC\\_NEVER](#), [l4\\_utcb\\_t](#) \*utcb=[l4\\_utcb\(\)](#)) noexcept

*Unmask the given interrupt line.*

## Additional Inherited Members

## Protected Types inherited from

[L4::Kobject\\_t< lcu, Irq\\_eoi, L4\\_PROTO\\_IRQ, Type\\_info::Demand\\_t< 1 > >](#)

- typedef [lcu](#) **Class**

*The target interface type (inheriting from [Kobject\\_t](#)).*

- typedef [Typeid::Iface< PROTO, lcu >](#) **\_\_Iface**

*The interface description for the derived class.*

- typedef [Typeid::Merge\\_list< Typeid::Iface\\_list< \\_\\_Iface >, typename Irq\\_eoi::\\_\\_Iface\\_list >](#) **\_\_Iface\_list**

*The list of all RPC interfaces provided directly or through inheritance.*

## Protected Member Functions inherited from

[L4::Kobject\\_t< lcu, Irq\\_eoi, L4\\_PROTO\\_IRQ, Type\\_info::Demand\\_t< 1 > >](#)

- [L4::Cap< Class > c](#) () const noexcept

*Get the capability to ourselves.*

## Static Protected Member Functions inherited from

[L4::Kobject\\_t< lcu, Irq\\_eoi, L4\\_PROTO\\_IRQ, Type\\_info::Demand\\_t< 1 > >](#)

- static void [\\_\\_check\\_protocols\\_\\_](#) () noexcept

*Helper to check for protocol conflicts.*

## 15.94.1 Detailed Description

C++ [Icu](#) interface, see [Interrupt controller](#) for the C interface.

### Note

"ICU" is short for "interrupt control unit".

This class defines the interface for interrupt controllers. It defines functions for binding [L4::Irq](#) objects to interrupt lines and other interrupt sources, as well as functions for masking and unmasking of interrupts.

To setup an interrupt line the following steps are required:

1. [set\\_mode\(\)](#) (optional if interrupt has a default mode)
2. [L4::Rcv\\_endpoint::bind\\_thread\(\)](#) or [L4::Rcv\\_endpoint::bind\\_snd\\_destination\(\)](#) to attach the [L4::Irq](#) object to a send destination.
3. [bind\(\)](#)
4. [unmask\(\)](#) to receive the first interrupt

For certain interrupt sources only some of these steps are necessary and supported, see [L4::Scheduler](#) and [L4::Vcon](#).

At most one [L4::Irq](#) object can be bound to a certain interrupt source and a certain [L4::Irq](#) object can be bound to at most one interrupt source.

### Include File

```
#include <l4/sys/icu>
```

Definition at line 250 of file [irq](#).

## 15.94.2 Member Function Documentation

### 15.94.2.1 bind()

```
l4_msgtag_t L4::Icu::bind (
    unsigned irqnum,
    L4::Cap< Triggerable > irq,
    l4_utcb_t * utcb = l4_utcb()) [inline], [noexcept]
```

Bind an interrupt line of an interrupt controller to an interrupt object.

### Parameters

<i>irqnum</i>	IRQ line at the ICU.
<i>irq</i>	IRQ object for the given IRQ line to bind to this ICU.
<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. See <a href="#">l4_utcb</a> .

## Returns

Syscall return tag. The caller should check the return value using [l4\\_error\(\)](#) to check for errors and to identify the correct method for unmasking the interrupt. Return values  $< 0$  indicate an error. A return value of 0 means a direct unmask via the IRQ object using [L4::irq::unmask](#). A return value of 1 means that the interrupt has to be unmasked via the ICU using [L4::icu::unmask](#).

## Return values

<a href="#">-L4_EINVAL</a>	<code>irq</code> is bound to an interrupt source.
<a href="#">-L4_EPERM</a>	Insufficient permissions; see precondition.

## Precondition


The capability `irq` must have the permission [L4\\_CAP\\_FPAGE\\_W](#).

In case the `irq` is already bound to an interrupt source, it is unbound first. In case the `irq` is bound and the interrupt source is bound to a different [L4::irq](#) object, only the unbinding happens. An [L4::irq](#) object that is bound to an interrupt source will get unbound if the [L4::irq](#) object is deleted.

Definition at line 310 of file [irq](#).

References [L4::Cap\\_base::cap\(\)](#), [L4::Kobject::cap\(\)](#), and [l4\\_icu\\_bind\\_u\(\)](#).

Here is the call graph for this function:



## 15.94.2.2 info()

```

l4_msgtag_t L4::Icu::info (
    l4_icu_info_t * info,
    l4_utcb_t * utcb = l4_utcb()) [inline], [noexcept]

```

Get information about the ICU features.

## Parameters

out	info	<a href="#">Info</a> structure to be filled with information.
-----	------	---

	<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. See <a href="#">l4_utcb</a> .
--	-------------	--

### Returns


Syscall return tag

Definition at line 345 of file [irq](#).


References [L4::Kobject::cap\(\)](#), [info\(\)](#), and [l4\\_icu\\_info\\_u\(\)](#).

Referenced by [L4Re::Event::get\\_axis\\_info\(\)](#), [L4Re::Event::get\\_stream\\_info\(\)](#), [L4Re::Event::get\\_stream\\_info\\_for\\_id\(\)](#), and [info\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 15.94.2.3 mask()

```

l4_msgtag_t L4::Icu::mask (
    unsigned irqnum,
    l4_umword_t * label = 0,
    l4_timeout_t to = L4_IPC_NEVER,
    l4_utcb_t * utcb = l4_utcb()) [inline], [noexcept]

```

Mask an IRQ line.

**Parameters**

<i>irqnum</i>	IRQ line at the ICU.
<i>label</i>	If NULL, this function is a send-only message to the ICU. If not NULL, this function will enter an open wait after sending the mask message and the received label is returned here.
<i>to</i>	The timeout-pair (send and receive) that shall be used for this operation. The receive timeout is used with a non-NULL <i>label</i> only.
<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. See <a href="#">l4_utcb</a> .


**Returns**

Syscall return tag. If *label* is NULL, this function performs an IPC send-only operation and there is no return value except [L4\\_MSGTAG\\_ERROR](#) indicating success or failure of the send operation. In this case use [l4\\_ipc\\_error\(\)](#) to check for errors and **do not** use [l4\\_error\(\)](#).

Definition at line 393 of file [irq](#).

References [L4::Kobject::cap\(\)](#), [l4\\_icu\\_mask\\_u\(\)](#), and [L4\\_IPC\\_NEVER](#).

Here is the call graph for this function:

**15.94.2.4 msi\_info()**

```

l4_msgtag_t L4::Icu::msi_info (
    l4_umword_t irqnum,
    l4_uint64_t source,
    l4_icu_msi_info_t * msi_info)
  
```

Get MSI info about IRQ.

**Parameters**

	<i>irqnum</i>	IRQ line at the ICU.
	<i>source</i>	Platform dependent requester ID for MSIs. On IA32 we use a 20bit source filter value as described in the Intel IRQ remapping specification.
out	<i>msi_info</i>	A <a href="#">l4_icu_msi_info_t</a> structure receiving the address and the data value to trigger this MSI.




**Returns**

Syscall return tag

References [msi\\_info\(\)](#).

Referenced by [msi\\_info\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:

**15.94.2.5 set\_mode()**

```

l4_msgtag_t L4::Icu::set_mode (
    unsigned irqnum,
    l4_umword_t mode,
    l4_utcb_t * utcb = l4_utcb()) [inline], [noexcept]
  
```

Set interrupt mode.

**Parameters**

<i>irqnum</i>	IRQ line at the ICU.
<i>mode</i>	Mode, see <a href="#">L4_irq_mode</a> .
<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. See <a href="#">l4_utcb</a> .


**Returns**

Syscall return tag

Definition at line 421 of file [irq](#).

References [L4::Kobject::cap\(\)](#), and [l4\\_icu\\_set\\_mode\\_u\(\)](#).

Here is the call graph for this function:

**15.94.2.6 unbind()**

```

l4_msgtag_t L4::Icu::unbind (
    unsigned irqnum,
    L4::Cap< Triggerable > irq,
    l4_utcb_t * utcb = l4_utcb()) [inline], [noexcept]
  
```

Remove binding of an interrupt line from the interrupt controller object.

**Parameters**

<i>irqnum</i>	IRQ line at the ICU.
<i>irq</i>	IRQ object to remove from the ICU.
<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. See <a href="#">l4_utcb</a> .


**Returns**

Syscall return tag

Definition at line 328 of file [irq](#).

References [L4::Cap\\_base::cap\(\)](#), [L4::Kobject::cap\(\)](#), and [l4\\_icu\\_unbind\\_u\(\)](#).

Here is the call graph for this function:



The documentation for this class was generated from the following file:


- [l4/sys/irq](#)

## 15.95 L4::lcu::Info Class Reference


This class encapsulates information about an ICU.

```
#include <irq>
```

Inheritance diagram for L4::lcu::Info:



Collaboration diagram for L4::Icu::Info:



### Public Member Functions

- bool **supports\_msi** () const noexcept  
*True, if the ICU has support for MSIs.*

### Additional Inherited Members

### Data Fields inherited from [l4\\_icu\\_info\\_t](#)

- unsigned [features](#)  
*Feature flags.*
- unsigned **nr\_irqs**  
*The number of IRQ lines supported by the ICU,.*
- unsigned **nr\_msis**  
*The number of MSI vectors supported by the ICU,.*

## 15.95.1 Detailed Description

This class encapsulates information about an ICU.

Definition at line [277](#) of file [irq](#).

The documentation for this class was generated from the following file:


- [l4/sys/irq](#)

## 15.96 L4::Invalid\_capability Class Reference


Indicates that an invalid object was invoked.

```
#include <l4/cxx/exceptions>
```

Inheritance diagram for L4::Invalid\_capability:



Collaboration diagram for L4::Invalid\_capability:



### Public Member Functions

- `Invalid_capability (Cap< void > const &o) noexcept`  
*Create an Invalid\_object exception for the Object o.*
- `char const * str () const noexcept` override  
*Return a human readable string for the exception.*
- `Cap< void > const & cap () const noexcept`  
*Get the object that caused the error.*

### Public Member Functions inherited from `L4::Base_exception`

- `virtual ~Base_exception () noexcept`  
*Destruction.*

## Public Member Functions inherited from L4::Exception\_tracer

- void const \*const \* **pc\_array** () const noexcept  
*Get the array containing the call trace.*
- int **frame\_count** () const noexcept  
*Get the number of entries that are valid in the call trace.*

## Additional Inherited Members

## Protected Member Functions inherited from L4::Base\_exception

- **Base\_exception** () noexcept  
*Create a base exception.*

## Protected Member Functions inherited from L4::Exception\_tracer

- **Exception\_tracer** () noexcept  
*Create a back trace.*

## 15.96.1 Detailed Description

Indicates that an invalid object was invoked.

An Object is invalid if it has L4\_INVALID\_ID as server L4 UID, or if the server does not know the object ID.

Definition at line 234 of file [exceptions](#).

## 15.96.2 Constructor & Destructor Documentation

### 15.96.2.1 Invalid\_capability()

```
L4::Invalid_capability::Invalid_capability (
    Cap< void > const & o) [inline], [explicit], [noexcept]
```

Create an Invalid\_object exception for the Object o.

#### Parameters

<b>o</b>	The object that caused the server side error.
----------	---

Definition at line 244 of file [exceptions](#).

### 15.96.3 Member Function Documentation

#### 15.96.3.1 cap()

```
Cap< void > const & L4::Invalid_capability::cap () const [inline], [noexcept]
```

Get the object that caused the error.

##### Returns

The object that caused the error on invocation.

Definition at line 253 of file [exceptions](#).

The documentation for this class was generated from the following file:

- [l4/cxx/exceptions](#)


## 15.97 L4::lo\_pager Class Reference

[lo\\_pager](#) interface.


```
#include <pager>
```



Inheritance diagram for L4::lo\_pager:



Collaboration diagram for L4::io\_pager:



### Public Member Functions

- [l4\\_msgtag\\_t](#) [io\\_page\\_fault](#) ([l4\\_fpage\\_t](#) io\_pfa, [l4\\_umword\\_t](#) pc, [L4::lpc::Rcv\\_fpage](#) rwin, [L4::lpc::Opt<L4::lpc::Snd\\_fpage & >](#) fp)  
*IO page fault protocol message.*

## 15.97.1 Detailed Description

[io\\_pager](#) interface.

### Note

This interface is IA32 specific.

This class defines the interface for handling IO page faults. IO page faults happen when a thread tries to access an IO port that it does not currently have access to.

Depending on the microkernel's implementation, IO page faults can be handled in two ways.

If the microkernel does not support IO page faults, this IO pagefault interface is not used. Instead, the microkernel sends an exception IPC to the thread's exception handler ([L4::Exception](#)), indicating a `GP` (exception number 13). The exception handler must consult the faulting instruction to determine the cause of the exception. This is the default in Fiasco.OC.

In contrast, if the microkernel supports IO page faults, the microkernel will generate an IO page fault message and send it to the thread's page fault handler (pager). The page fault handler can implement this interface to handle the IO page faults.

### Note

A program may use this mechanism to implement a lazy IO port access scheme.

The page fault and exception handlers are set with the [L4::Thread::control](#) interface.

Definition at line 50 of file [pager](#).

## 15.97.2 Member Function Documentation

### 15.97.2.1 io\_page\_fault()

```
l4_msgtag_t L4::Io_pager::io_page_fault (
    l4_fpage_t io_pfa,
    l4_umword_t pc,
    L4::Ipc::Rcv_fpage rwin,
    L4::Ipc::Opt< L4::Ipc::Snd_fpage & > fp)
```

IO page fault protocol message.

#### Parameters

	<i>io_pfa</i>	Flexpage describing the faulting IO-port.
	<i>pc</i>	Faulting program counter.
	<i>rwin</i>	The receive window for a flexpage mapping.
out	<i>fp</i>	Optional: flexpage descriptor to send to the task raising the page fault.

#### Returns

System call message tag; use [l4\\_error\(\)](#) to check for errors.

IO-port fault messages are usually generated by the kernel and an IO-page-fault handler needs to be in place to handle such faults and generate a reply, potentially filling in *fp*.

The documentation for this class was generated from the following file:


- [l4/sys/pager](#)

## 15.98 L4::lomu Class Reference


Interface for IO-MMUs used for DMA remapping.

```
#include <iommu>
```

Inheritance diagram for L4::lommu:



Collaboration diagram for L4::lomu:



### Public Member Functions

- `l4_msgtag_t bind (l4_uint64_t src_id, lpc::Cap< Task > dma_space)`  
Associate *dma\_space* with the set of device(s) specified by *src\_id*.
- `l4_msgtag_t unbind (l4_uint64_t src_id, lpc::Cap< Task > dma_space)`  
Remove the association of the given DMA address space from the device(s) specified by *src\_id*.

### 15.98.1 Detailed Description

Interface for IO-MMUs used for DMA remapping.

#### Note

This interface is only present in the kernel if the kernel detected an IOMMU during boot.

This interface allows to associate a DMA address space with a platform dependent set of devices. The kernel automatically keeps the memory spaces of associated DMA spaces in sync with the respective page table structures in the IOMMU.

Definition at line 21 of file [lomu](#).

## 15.98.2 Member Function Documentation

### 15.98.2.1 bind()

```
l4_msgtag_t L4::Iommu::bind (
    l4_uint64_t src_id,
    Ipc::Cap< Task > dma_space)
```

Associate `dma_space` with the set of device(s) specified by `src_id`.

Updates the respective page table structures in the IOMMU and keeps them in sync when memory is mapped to the `dma_space` or revoked from it.

#### Parameters

<i>src_id</i>	Platform dependent source ID specifying the set of devices that shall use <code>dma_space</code> for DMA remapping.
<i>dma_space</i>	The DMA space ( <a href="#">L4::Task</a> created with <code>L4_PROTO_DMA_SPACE</code> ) providing the mappings that shall be used for the device(s).

References [bind\(\)](#).

Referenced by [bind\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 15.98.2.2 unbind()

```
l4_msgtag_t L4::Iommu::unbind (
    l4_uint64_t src_id,
    Ipc::Cap< Task > dma_space)
```

Remove the association of the given DMA address space from the device(s) specified by `src_id`.

Clear the respective page stable structures in the IOMMU.

#### Parameters

<i>src_id</i>	Platform dependent source ID specifying the set of devices that shall no longer use <code>dma_space</code> for DMA remapping.
<i>dma_space</i>	The DMA space formerly associated with <a href="#">bind()</a> .

References [unbind\(\)](#).

Referenced by [unbind\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



The documentation for this class was generated from the following file:


- `l4/sys/iommu`

## 15.99 L4::IOModifier Class Reference

Modifier class for the IO stream.

```
#include <basic_ostream>
```

Collaboration diagram for L4::IOModifier:



### 15.99.1 Detailed Description

Modifier class for the IO stream.

An IO Modifier can be used to change properties of an IO stream for example the number format.

Definition at line 22 of file [basic\\_ostream](#).

The documentation for this class was generated from the following file:

- [l4/cxx/basic\\_ostream](#)


## 15.100 L4::lpc::Array< ELEM\_TYPE, LEN\_TYPE > Struct Template Reference

[Array](#) data type for dynamically sized arrays in RPCs.


```
#include <ipc_array>
```



Inheritance diagram for L4::lpc::Array< ELEM\_TYPE, LEN\_TYPE >:



Collaboration diagram for L4::lpc::Array< ELEM\_TYPE, LEN\_TYPE >:



## Public Member Functions

- **Array** ()  
*Make array.*
- **Array** (LEN\_TYPE length, ELEM\_TYPE \*data)  
*Make array from length and data pointer.*
- **Array** (typename Non\_const< ELEM\_TYPE >::type const &other)  
*Make a const array from a non-const array.*

### 15.100.1 Detailed Description

```
template<typename ELEM_TYPE, typename LEN_TYPE = Array_len_default>
struct L4::lpc::Array< ELEM_TYPE, LEN_TYPE >
```

[Array](#) data type for dynamically sized arrays in RPCs.

### Template Parameters

<i>ELEM_TYPE</i>	The data type of an array element, should be 'const' when used as input.
<i>LEN_TYPE</i>	Data type used to store the number of elements in the array.

An [Array](#) generally encapsulates a data pointer and a length (number of elements). [Array](#) does *not* provide any storage for the data itself. The storage is either provided by a client-side caller or in the case of [Array\\_ref](#) is the message itself.

Arrays can be used as input or as output arguments, when used as input *ELEM\_TYPE* should be qualified *const*, when used as output a reference to an array must be used and the *ELEM\_TYPE* must *not* be qualified *const*. It is the caller's responsibility to provide an array buffer of sufficient length. If a message from the server is too large it will be silently truncated.

If backward compatibility with `lpc::Stream` is required, then *LEN\_TYPE* must be `unsigned long`.

Definition at line 81 of file [ipc\\_array](#).

The documentation for this struct was generated from the following file:


- `l4/sys/cxx/ipc_array`

## 15.101 L4::lpc::Array\_in\_buf< ELEM\_TYPE, LEN\_TYPE, MAX > Struct Template Reference


Server-side copy in buffer for [Array](#).

```
#include <ipc_array>
```

Inheritance diagram for L4::lpc::Array\_in\_buf< ELEM\_TYPE, LEN\_TYPE, MAX >:



Collaboration diagram for L4::lpc::Array\_in\_buf< ELEM\_TYPE, LEN\_TYPE, MAX >:



## Public Member Functions

- void **copy\_in** (const\_array a)  
*copy in data from a source array*
- **Array\_in\_buf** (const\_array a)  
*Make [Array\\_in\\_buf](#) from a const array.*
- **Array\_in\_buf** (array a)  
*Make [Array\\_in\\_buf](#) from a non-const array.*

## Data Fields

- ELEM\_TYPE **data** [MAX]  
*The data elements.*
- LEN\_TYPE **length**  
*The length of the array.*

### 15.101.1 Detailed Description

```
template<typename ELEM_TYPE, typename LEN_TYPE = Array_len_default, LEN_TYPE MAX = (L4_↔
UTCB_GENERIC_DATA_SIZE * sizeof(I4_umword_t)) / sizeof(ELEM_TYPE)>
struct L4::lpc::Array_in_buf< ELEM_TYPE, LEN_TYPE, MAX >
```

Server-side copy in buffer for [Array](#).

## Template Parameters

<i>ELEM_TYPE</i>	Data type of an array element.
<i>LEN_TYPE</i>	Data type for the number of elements in the array.
<i>MAX</i>	The maximum number of elements in the buffer. If the actual message is longer than the buffer, it will be silently truncated.

This type is assignment compatible to [Array\\_ref<ELEM\\_TYPE, LEN\\_TYPE>](#) and provides a transparent server-side copy-in mechanism for array parameters. The [Array\\_in\\_buf](#) provides the storage for the array data and receives a copy of the data passed to the server-function.

Definition at line 126 of file [ipc\\_array](#).

The documentation for this struct was generated from the following file:

- I4/sys/cxx/ipc\_array



**Note**

Use [Array](#) for normal RPC interfaces, [Array\\_ref](#) is usually used as server-side argument, see [Array](#).

**Template Parameters**

<i>ELEM_TYPE</i>	The data type of an array element, should be 'const' when used as input.
<i>LEN_TYPE</i>	Data type used to store the number of elements in the array.

Definition at line 28 of file [ipc\\_array](#).

The documentation for this struct was generated from the following file:


- l4/sys/cxx/ipc\_array

## 15.103 L4::lpc::As\_value< T > Struct Template Reference

Pass the argument as plain data value.

```
#include <ipc_types>
```

Collaboration diagram for L4::lpc::As\_value< T >:



### 15.103.1 Detailed Description

```
template<typename T>
struct L4::lpc::As_value< T >
```

Pass the argument as plain data value.

**Template Parameters**

<i>T</i>	The type of the original argument.
----------	------------------------------------

[As\\_value<T>](#) is used when *T* would be otherwise interpreted specially, for example as flexpage. When using [As\\_value<>](#) then the argument is transmitted as plain data element.

Definition at line 116 of file [ipc\\_types](#).

The documentation for this struct was generated from the following file:


- l4/sys/cxx/ipc\_types

## 15.104 L4::lpc::Call Struct Reference


RPC attribute for a standard RPC call.

```
#include <ipc_iface>
```

Inheritance diagram for L4::lpc::Call:



Collaboration diagram for L4::lpc::Call:



### 15.104.1 Detailed Description

RPC attribute for a standard RPC call.

This is the default for the *FLAGS* parameter for L4::lpc::Msg::Rpc\_call L4::lpc::Msg::Rpc\_inline\_call templates and declares the RPC to have default call semantics and timeouts.

Examples:

```
L4_RPC(l4_ret_t, send, (unsigned value), L4::lpc::Call);
```



which is equivalent to:

```
L4_RPC(l4_ret_t, send, (unsigned value));
```

Definition at line 239 of file [ipc\\_iface](#).

The documentation for this struct was generated from the following file:


- [l4/sys/cxx/ipc\\_iface](#)

## 15.105 L4::lpc::Call\_t< RIGHTS > Struct Template Reference


RPC attribute for an RPC call with required rights.

```
#include <ipc_iface>
```

Inheritance diagram for L4::lpc::Call\_t< RIGHTS >:



Collaboration diagram for L4::lpc::Call\_t< RIGHTS >:



### 15.105.1 Detailed Description

```
template<unsigned RIGHTS>
struct L4::lpc::Call_t< RIGHTS >
```

RPC attribute for an RPC call with required rights.

#### Template Parameters

<i>RIGHTS</i>	The capability rights required for this call. <a href="#">L4_CAP_FPAGE_W</a> and <a href="#">L4_CAP_FPAGE_S</a> are checked within the server (and <a href="#">-L4_EPERM</a> shall be returned if the caller has insufficient rights). <a href="#">L4_CAP_FPAGE_R</a> is always on but might be specified for documentation purposes. Other rights cannot be used in this context, because they cannot be checked at the server side.
---------------	---

Examples:

```
L4_RPC(l4_ret_t, func, (unsigned value), L4::lpc::Call_t<L4_CAP_FPAGE_RW>);
```

Definition at line 270 of file [ipc\\_iface](#).

The documentation for this struct was generated from the following file:


- [l4/sys/cxx/ipc\\_iface](#)

## 15.106 L4::lpc::Call\_zero\_send\_timeout Struct Reference


RPC attribute for an RPC call, with zero send timeout.

```
#include <ipc_iface>
```

Inheritance diagram for L4::lpc::Call\_zero\_send\_timeout:



Collaboration diagram for L4::lpc::Call\_zero\_send\_timeout:



### 15.106.1 Detailed Description

RPC attribute for an RPC call, with zero send timeout.

Definition at line 249 of file [ipc\\_iface](#).

The documentation for this struct was generated from the following file:


- [l4/sys/cxx/ipc\\_iface](#)

## 15.107 L4::lpc::Cap< T > Class Template Reference

Capability type for RPC interfaces (see [L4::Cap<T>](#)).

```
#include <ipc_types>
```

Inheritance diagram for L4::lpc::Cap< T >:



Collaboration diagram for L4::lpc::Cap< T >:

L4::lpc::Cap< T >
<ul style="list-style-type: none"> <li>+ Cap()</li> <li>+ Cap()</li> <li>+ Cap()</li> <li>+ Cap()</li> <li>+ Cap()</li> <li>+ cap()</li> <li>+ rights()</li> <li>+ fpage()</li> <li>+ is_valid()</li> <li>+ from_ci()</li> </ul>

## Public Types

- enum { [Rights\\_mask](#) = 0xff , [Cap\\_mask](#) = L4\_CAP\_MASK }

## Public Member Functions

- template<typename O>  
**Cap** (Cap< O > const &o) noexcept  
*Make copy with conversion.*
- Cap** ([L4::Cap](#)< T > [cap](#)) noexcept  
*Make a [Cap](#) from [L4::Cap](#)<T>, with minimal rights.*
- template<typename O>  
**Cap** ([L4::Cap](#)< O > [cap](#)) noexcept  
*Make IPC [Cap](#) from [L4::Cap](#) with conversion (and minimal rights).*
- Cap** () noexcept  
*Make an invalid cap.*
- Cap** ([L4::Cap](#)< T > [cap](#), unsigned char [rights](#)) noexcept  
*Make a [Cap](#) from [L4::Cap](#)<T> with the given rights.*
- [L4::Cap](#)< T > **cap** () const noexcept  
*Return the [L4::Cap](#)<T> of this [Cap](#).*
- unsigned **rights** () const noexcept  
*Return the rights bits stored in this IPC cap.*
- [L4::lpc::Snd\\_fpage](#) **fpage** () const noexcept  
*Return the send flexpage for this [Cap](#) (see [l4\\_fpage\\_t](#)).*
- bool **is\_valid** () const noexcept  
*Return true if this [Cap](#) is valid.*

## Static Public Member Functions

- static Cap [from\\_ci](#) ([l4\\_cap\\_idx\\_t](#) c) noexcept  
*Create an IPC capability from a C capability index plus rights.*

### 15.107.1 Detailed Description

```
template<typename T>
class L4::lpc::Cap< T >
```

Capability type for RPC interfaces (see [L4::Cap<T>](#)).

#### Template Parameters

<i>T</i>	type of the interface referenced by the capability.
----------	---

In contrast to [L4::Cap<T>](#) this type additionally stores a rights mask that shall be used when the capability is transferred to the receiver. This allows to apply restrictions to the transferred capability in the form of a subset of the rights possessed by the sender.

See also

[L4::lpc::make\\_cap\(\)](#)

Definition at line 698 of file [ipc\\_types](#).

### 15.107.2 Member Enumeration Documentation

#### 15.107.2.1 anonymous enum

```
template<typename T>
anonymous enum
```

#### Enumerator

Rights_mask	Mask for rights bits stored internally. <a href="#">L4_FPAGE_RIGHTS_MASK</a>   <a href="#">L4_FPAGE_C_NO_REF_CNT</a>   <a href="#">L4_FPAGE_C_OBJ_RIGHTS</a> ).
Cap_mask	Mask for significant capability bits. (incl. the invalid bit to support invalid caps)

Definition at line 704 of file [ipc\\_types](#).

### 15.107.3 Constructor & Destructor Documentation

#### 15.107.3.1 Cap()

```
template<typename T>
L4::Ipc::Cap< T >::Cap (
    L4::Cap< T > cap,
    unsigned char rights) [inline], [noexcept]
```

Make a [Cap](#) from [L4::Cap<T>](#) with the given rights.

##### Parameters

<i>cap</i>	Capability to be sent.
<i>rights</i>	Rights to be sent. Consists of <a href="#">L4_fpage_rights</a> and <a href="#">Attributes and additional permissions for object send items</a> .

Definition at line 750 of file [ipc\\_types](#).

### 15.107.4 Member Function Documentation

#### 15.107.4.1 from\_ci()

```
template<typename T>
Cap L4::Ipc::Cap< T >::from_ci (
    l4_cap_idx_t c) [inline], [static], [noexcept]
```

Create an IPC capability from a C capability index plus rights.

##### Parameters

<i>c</i>	C capability index with the lowest 8 bits used as rights for the map operation (see <a href="#">L4_fpage_rights</a> ).
----------	--

Definition at line 758 of file [ipc\\_types](#).

The documentation for this class was generated from the following file:


- [l4/sys/cxx/ipc\\_types](#)

## 15.108 L4::lpc::Gen\_fpage Class Reference

Generic RPC base for typed message items.

```
#include <ipc_types>
```

Inheritance diagram for L4::lpc::Gen\_fpage:





Collaboration diagram for L4::lpc::Gen\_fpage:

L4::lpc::Gen_fpage
<ul style="list-style-type: none"> <li>+ Gen_fpage()</li> <li>+ data()</li> <li>+ base_x()</li> </ul>

## Public Types

- enum [Type](#) { [Special](#) = L4\_FPAGE\_SPECIAL << 4 , [Memory](#) = L4\_FPAGE\_MEMORY << 4 , [Io](#) = L4\_FPAGE\_IO << 4 , [Obj](#) = L4\_FPAGE\_OBJ << 4 }
- Type of mapping object, see [L4\\_fpage\\_type](#).*

## Public Member Functions

- **Gen\_fpage** ([l4\\_umword\\_t](#) base, [l4\\_umword\\_t](#) data) noexcept  
*Construct from raw values.*
- [l4\\_umword\\_t](#) **data** () const noexcept  
*Return the raw flexpage descriptor.*
- [l4\\_umword\\_t](#) **base\_x** () const noexcept  
*Return the raw base descriptor.*

## 15.108.1 Detailed Description

Generic RPC base for typed message items.

Definition at line 286 of file [ipc\\_types](#).

## 15.108.2 Member Enumeration Documentation

### 15.108.2.1 Type

enum [L4::lpc::Gen\\_fpage::Type](#)

[Type](#) of mapping object, see [L4\\_fpage\\_type](#).

**Enumerator**

Special	Special flexpage, either <a href="#">l4_fpage_invalid()</a> or <a href="#">l4_fpage_all()</a> ; only supported by selected interfaces.
Memory	Flexpage for memory spaces.
Io	Flexpage for I/O port spaces.
Obj	Flexpage for object spaces.

Definition at line [290](#) of file [ipc\\_types](#).

The documentation for this class was generated from the following file:


- [l4/sys/cxx/ipc\\_types](#)

**15.109 L4::lpc::ln\_out< T > Struct Template Reference**

Mark an argument as in-out argument.

```
#include <ipc_types>
```

Collaboration diagram for L4::lpc::ln\_out< T >:

**15.109.1 Detailed Description**

```
template<typename T>
struct L4::lpc::ln_out< T >
```

Mark an argument as in-out argument.

**Template Parameters**

<i>T</i>	The original argument type, usually a pointer or a reference.
----------	---

[ln\\_out<>](#) is used when an otherwise output-only value shall also be used as input value.

Definition at line [41](#) of file [ipc\\_types](#).

The documentation for this struct was generated from the following file:


- [l4/sys/cxx/ipc\\_types](#)

## 15.110 L4::lpc::lostream Class Reference


Input/Output stream for IPC [un]marshalling.

```
#include <ipc_stream>
```

Inheritance diagram for L4::lpc::lostream:



Collaboration diagram for L4::ipc::lostream:



## Public Member Functions

- `lostream (l4_utcb_t *utcb)`  
Create an IPC IO stream with a single message buffer.
- `void reset ()`  
Reset the stream to its initial state.

**IPC operations.**

- `l4_msgtag_t` call (`l4_cap_idx_t` dst, `l4_timeout_t` timeout, long proto=0)  
*Do an IPC call using the message in the output stream and receive the reply in the input stream.*
- `l4_msgtag_t` reply\_and\_wait (`l4_umword_t` \*src\_dst, long proto=0)  
*Do an IPC reply and wait.*
- `l4_msgtag_t` reply\_and\_wait (`l4_umword_t` \*src\_dst, `l4_timeout_t` timeout, long proto=0)  
*Do an IPC reply and wait.*

**Get/Put functions.**

These functions are basically used to implement the insertion operators (<<) and should not be called directly.

- template<typename T>  
unsigned long `get` (T \*buf, unsigned long elems)  
*Copy out an array of type T with size elements.*
- template<typename T>  
unsigned long `get` (Msg\_ptr< T > const &buf, unsigned long elems=1)  
*Read one size elements of type T from the stream and return a pointer.*
- template<typename T>  
bool `get` (T &v)  
*Extract a single element of type T from the stream.*
- template<typename T>  
bool `put` (T \*buf, unsigned long size)  
*Put an array with size elements of type T into the stream.*
- template<typename T>  
bool `put` (T const &v)  
*Insert an element of type T into the stream.*

**Public Member Functions inherited from L4::lpc::lstream**

- `lstream` (`l4_utcb_t` \*utcb)  
*Create an input stream for the given message buffer.*
- void `reset` ()  
*Reset the stream to empty, and ready for `receive()`/`wait()`.*
- template<typename T>  
bool `has_more` (unsigned long count=1)  
*Check whether a value of type T can be obtained from the stream.*
- `l4_utcb_t` \* `utcb` () const  
*Return utcb pointer.*
- template<typename T>  
unsigned long `get` (T \*buf, unsigned long elems)  
*Copy out an array of type T with size elements.*
- template<typename T>  
void `skip` (unsigned long elems)  
*Skip size elements of type T in the stream.*
- template<typename T>  
unsigned long `get` (Msg\_ptr< T > const &buf, unsigned long elems=1)  
*Read one size elements of type T from the stream and return a pointer.*
- template<typename T>  
bool `get` (T &v)  
*Extract a single element of type T from the stream.*
- `l4_msgtag_t` tag () const

*Get the message tag of a received IPC.*

- [l4\\_msgtag\\_t](#) & [tag](#) ()

*Get the message tag of a received IPC.*

- [l4\\_msgtag\\_t](#) wait ([l4\\_umword\\_t](#) \*src)

*Wait for an incoming message from any sender.*

- [l4\\_msgtag\\_t](#) wait ([l4\\_umword\\_t](#) \*src, [l4\\_timeout\\_t](#) timeout)

*Wait for an incoming message from any sender.*

- [l4\\_msgtag\\_t](#) receive ([l4\\_cap\\_idx\\_t](#) src)

*Wait for a message from the specified sender.*

## Public Member Functions inherited from [L4::lpc::Ostream](#)

- **Ostream** ([l4\\_utcb\\_t](#) \*utcb)

*Create an IPC output stream using the given message buffer [utcb](#).*

- void **reset** ()

*Reset the stream to empty, same state as a newly created stream.*

- [l4\\_utcb\\_t](#) \* **utcb** () const

*Return utcb pointer.*

- template<typename T>

bool **put** (T \*buf, unsigned long size)

*Put an array with *size* elements of type *T* into the stream.*

- template<typename T>

bool **put** (T const &v)

*Insert an element of type *T* into the stream.*

- [l4\\_msgtag\\_t](#) **tag** () const

*Extract the [L4](#) message tag from the stream.*

- [l4\\_msgtag\\_t](#) & **tag** ()

*Extract a reference to the [L4](#) message tag from the stream.*

- [l4\\_msgtag\\_t](#) **send** ([l4\\_cap\\_idx\\_t](#) dst, long proto=0, unsigned flags=0)

*Send the message via IPC to the given receiver.*

### 15.110.1 Detailed Description

Input/Output stream for IPC [un]marshalling.

The [lpc::lostream](#) is part of the AW Env IPC framework as well as [lpc::lstream](#) and [lpc::Ostream](#). In particular an [lpc::lostream](#) is a combination of an [lpc::lstream](#) and an [lpc::Ostream](#). It can use either a single message buffer for receiving and sending messages or a pair of a receive and a send buffer. The stream also supports combined IPC operations such as [call\(\)](#) and [reply\\_and\\_wait\(\)](#), which can be used to implement RPC functionality.

#### Examples

[examples/libs/l4re/c++/shared\\_ds/ds\\_srv.cc](#), [examples/libs/l4re/streammap/client.cc](#), and [examples/libs/l4re/streammap/server.cc](#).

Definition at line 789 of file [ipc\\_stream](#).

## 15.110.2 Constructor & Destructor Documentation

### 15.110.2.1 Iostream()

```
L4::Ipc::Iostream::Iostream (
    l4_utcb_t * utcb) [inline], [explicit]
```

Create an IPC IO stream with a single message buffer.

#### Parameters


<i>utcb</i>	The message buffer used as backing store.
-------------	---

The created IO stream uses the same message buffer for sending and receiving IPC messages.

Definition at line 801 of file [ipc\\_stream](#).

References [L4::Ipc::Istream::Istream\(\)](#), and [L4::Ipc::Ostream::Ostream\(\)](#).

Here is the call graph for this function:



## 15.110.3 Member Function Documentation

### 15.110.3.1 call()

```
l4_msgtag_t L4::Ipc::Iostream::call (
    l4_cap_idx_t dst,
    l4_timeout_t timeout,
    long proto = 0) [inline]
```

Do an IPC call using the message in the output stream and receive the reply in the input stream.

#### Parameters

<i>dst</i>	The destination to call.
<i>timeout</i>	The IPC timeout for the call.
<i>proto</i>	The protocol value to use in the message tag.

**Returns**

The result tag of the IPC operation.

This is a combined IPC operation consisting of a send and a receive to/from the given destination `dst`.

A call is usually used by clients for RPCs to a server.


**Examples**

[examples/libs/l4re/streammap/client.cc](#).

Definition at line 966 of file [ipc\\_stream](#).

References [l4\\_ipc\\_call\(\)](#), and [L4::lpc::lstream::tag\(\)](#).

Here is the call graph for this function:

**15.110.3.2 get() [1/3]**

```

template<typename T>
unsigned long L4::lpc::lstream::get (
    Msg_ptr< T > const & buf,
    unsigned long elems = 1) [inline]
  
```

Read one size elements of type T from the stream and return a pointer.

**Parameters**

<i>buf</i>	A <a href="#">Msg_ptr</a> that is actually set to point to the element in the stream.
<i>elems</i>	Number of elements to extract (default is 1).

**Returns**

The number of elements extracted.

In contrast to a normal get, this version does actually not copy the data but returns a pointer to the data.

See [operator>>\(\)](#)

Definition at line 439 of file [ipc\\_stream](#).



### 15.110.3.3 `get()` [2/3]

```
template<typename T>
bool L4::Ipc::Istream::get (
    T & v) [inline]
```

Extract a single element of type T from the stream.

#### Parameters

<i>out</i>	<i>v</i>	The element.
------------	----------	--------------

#### Return values

<i>true</i>	An element was successfully extracted.
<i>false</i>	An element could not be extracted.

See [operator>>\(\)](#)

Definition at line 464 of file [ipc\\_stream](#).

### 15.110.3.4 `get()` [3/3]

```
template<typename T>
unsigned long L4::Ipc::Istream::get (
    T * buf,
    unsigned long elems) [inline]
```

Copy out an array of type T with *size* elements.

#### Parameters

<i>buf</i>	Pointer to a buffer for size elements of type T.
<i>elems</i>	Number of elements of type T to copy out.

#### Returns

The number of elements copied out.

See [operator>>\(\)](#)

Definition at line 394 of file [ipc\\_stream](#).

**15.110.3.5 put()** [1/2]

```
template<typename T>
bool L4::Ipc::Ostream::put (
    T * buf,
    unsigned long size) [inline]
```

Put an array with *size* elements of type *T* into the stream.

**Parameters**

<i>buf</i>	A pointer to the array to insert into the buffer.
<i>size</i>	The number of elements in the array.

Definition at line 660 of file [ipc\\_stream](#).

**15.110.3.6 put()** [2/2]

```
template<typename T>
bool L4::Ipc::Ostream::put (
    T const & v) [inline]
```

Insert an element of type *T* into the stream.

**Parameters**

<i>v</i>	The element to insert.
----------	------------------------

Definition at line 678 of file [ipc\\_stream](#).

**15.110.3.7 reply\_and\_wait()** [1/2]

```
l4_msgtag_t L4::Ipc::Iostream::reply_and_wait (
    l4_umword_t * src_dst,
    l4_timeout_t timeout,
    long proto = 0) [inline]
```

Do an IPC reply and wait.

**Parameters**

<i>in, out</i>	<i>src_dst</i>	Input: the destination for the send operation. Output: the source of the received message.
	<i>timeout</i>	Timeout used for IPC.
	<i>proto</i>	Protocol to use.

**Returns**

The result tag of the IPC operation.


This is a combined IPC operation consisting of a send operation and an open wait for any message.

A reply and wait is usually used by servers that reply to a client and wait for the next request by any other client.

Definition at line 981 of file [ipc\\_stream](#).

References [l4\\_ipc\\_reply\\_and\\_wait\(\)](#), and [L4::lpc::lstream::tag\(\)](#).

Here is the call graph for this function:

**15.110.3.8 reply\_and\_wait() [2/2]**

```

l4_msgtag_t L4::lpc::lstream::reply_and_wait (
    l4_umword_t * src_dst,
    long proto = 0) [inline]
  
```

Do an IPC reply and wait.

**Parameters**

<i>in, out</i>	<i>src_dst</i>	Input: the destination for the send operation. Output: the source of the received message.
	<i>proto</i>	Protocol to use.

**Returns**

The result tag of the IPC operation.

This is a combined IPC operation consisting of a send operation and an open wait for any message.


A reply and wait is usually used by servers that reply to a client and wait for the next request by any other client.

Definition at line 874 of file [ipc\\_stream](#).


References [L4\\_IPC\\_SEND\\_TIMEOUT\\_0](#), and [reply\\_and\\_wait\(\)](#).

Referenced by [reply\\_and\\_wait\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 15.110.3.9 reset()

```
void L4::Ipc::Iostream::reset () [inline]
```


Reset the stream to its initial state.

Input as well as the output stream are reset.

Definition at line 815 of file [ipc\\_stream](#).

References [L4::lpc::Istream::reset\(\)](#), and [L4::lpc::Ostream::reset\(\)](#).

Here is the call graph for this function:



The documentation for this class was generated from the following file:


- [l4/cxx/ipc\\_stream](#)

## 15.111 L4::lpc::Istream Class Reference

Input stream for IPC unmarshalling.

```
#include <ipc_stream>
```

Inheritance diagram for L4::lpc::Istream:



Collaboration diagram for L4::lpc::Istream:



## Public Member Functions

- `Istream (l4_utcb_t *utcb)`  
Create an input stream for the given message buffer.
- `void reset ()`  
Reset the stream to empty, and ready for `receive()/wait()`.

- `template<typename T>`  
`bool has_more (unsigned long count=1)`  
*Check whether a value of type T can be obtained from the stream.*
- `l4_utcb_t * utcb () const`  
*Return utcb pointer.*

#### Get/Put Functions.

- `template<typename T>`  
`unsigned long get (T *buf, unsigned long elems)`  
*Copy out an array of type T with size elements.*
- `template<typename T>`  
`void skip (unsigned long elems)`  
*Skip size elements of type T in the stream.*
- `template<typename T>`  
`unsigned long get (Msg_ptr< T > const &buf, unsigned long elems=1)`  
*Read one size elements of type T from the stream and return a pointer.*
- `template<typename T>`  
`bool get (T &v)`  
*Extract a single element of type T from the stream.*
- `l4_msgtag_t tag () const`  
*Get the message tag of a received IPC.*
- `l4_msgtag_t & tag ()`  
*Get the message tag of a received IPC.*

#### IPC operations.

- `l4_msgtag_t wait (l4_umword_t *src)`  
*Wait for an incoming message from any sender.*
- `l4_msgtag_t wait (l4_umword_t *src, l4_timeout_t timeout)`  
*Wait for an incoming message from any sender.*
- `l4_msgtag_t receive (l4_cap_idx_t src)`  
*Wait for a message from the specified sender.*

### 15.111.1 Detailed Description

Input stream for IPC unmarshalling.

`lpc::lstream` is part of the dynamic IPC marshalling infrastructure, as well as `lpc::Ostream` and `lpc::lostream`.

`lpc::lstream` is an input stream supporting extraction of values from an IPC message buffer. A received IPC message can be unmarshalled using the usual extraction operator (>>).

There exist some special wrapper classes to extract arrays (see `lpc_buf_cp_in` and `lpc_buf_in`) and indirect strings (see `Msg_in_buffer` and `Msg_io_buffer`).

Definition at line 334 of file `ipc_stream`.

## 15.111.2 Constructor & Destructor Documentation

### 15.111.2.1 Istream()

```
L4::Ipc::Istream::Istream (
    l4_utcb_t * utcb) [inline]
```

Create an input stream for the given message buffer.

The given message buffer is used for IPC operations [wait\(\)](#)/[receive\(\)](#) and received data can be extracted using the `>>` operator afterwards. In the case of indirect message parts a buffer of type `Msg_in_buffer` must be inserted into the stream before the IPC operation and contains received data afterwards.

#### Parameters

<i>utcb</i>	The message buffer to receive IPC messages.
-------------	---

Definition at line [348](#) of file [ipc\\_stream](#).


References [utcb\(\)](#).

Referenced by [L4::Ipc::lostream::lostream\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:





### 15.111.3 Member Function Documentation

#### 15.111.3.1 `get()` [1/3]

```
template<typename T>
unsigned long L4::lpc::Istream::get (
    Msg_ptr< T > const & buf,
    unsigned long elems = 1) [inline]
```

Read one size elements of type T from the stream and return a pointer.

##### Parameters

<i>buf</i>	A <a href="#">Msg_ptr</a> that is actually set to point to the element in the stream.
<i>elems</i>	Number of elements to extract (default is 1).

##### Returns

The number of elements extracted.

In contrast to a normal `get`, this version does actually not copy the data but returns a pointer to the data.

See [operator>>\(\)](#)

Definition at line 439 of file [ipc\\_stream](#).

References [has\\_more\(\)](#), and [L4\\_UNLIKELY](#).

Here is the call graph for this function:



#### 15.111.3.2 `get()` [2/3]

```
template<typename T>
bool L4::lpc::Istream::get (
    T & v) [inline]
```

Extract a single element of type T from the stream.

##### Parameters

out	v	The element.
-----	---	--------------

### Return values

<i>true</i>	An element was successfully extracted.
<i>false</i>	An element could not be extracted.

See [operator>>\(\)](#)

Definition at line 464 of file [ipc\\_stream](#).

References [has\\_more\(\)](#), and [L4\\_UNLIKELY](#).

Here is the call graph for this function:



### 15.111.3.3 get() [3/3]

```

template<typename T>
unsigned long L4::Ipc::Istream::get (
    T * buf,
    unsigned long elems) [inline]
  
```

Copy out an array of type T with `size` elements.

### Parameters

<i>buf</i>	Pointer to a buffer for <code>size</code> elements of type T.
<i>elems</i>	Number of elements of type T to copy out.

### Returns

The number of elements copied out.

See [operator>>\(\)](#)

Definition at line 394 of file [ipc\\_stream](#).


References [has\\_more\(\)](#), and [L4\\_UNLIKELY](#).

Referenced by [operator>>\(\)](#), [operator>>\(\)](#), [operator>>\(\)](#), [operator>>\(\)](#), and [operator>>\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



#### 15.111.3.4 receive()

```
l4_msgtag_t L4::Ipc::Istream::receive (  
    l4_cap_idx_t src) [inline]
```

Wait for a message from the specified sender.

##### Parameters

<i>src</i>	The sender id to receive from.
------------	--------------------------------

#### Returns

The IPC result tag ([l4\\_msgtag\\_t](#)).


This is commonly known as 'closed wait'.

Definition at line [572](#) of file [ipc\\_stream](#).


References [L4\\_IPC\\_NEVER](#), and [receive\(\)](#).

Referenced by [receive\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



#### 15.111.3.5 reset()

```
void L4::Ipc::Istream::reset () [inline]
```


Reset the stream to empty, and ready for [receive\(\)/wait\(\)](#).

The stream is reset to the same state as on its creation.

Definition at line [358](#) of file [ipc\\_stream](#).

Referenced by [L4::Ipc::Istream::reset\(\)](#).

Here is the caller graph for this function:



### 15.111.3.6 skip()

```
template<typename T>
void L4::Ipc::Istream::skip (
    unsigned long elems) [inline]
```

Skip size elements of type T in the stream.

#### Parameters

<i>elems</i>	Number of elements to skip.
--------------	-----------------------------

Definition at line 414 of file [ipc\\_stream](#).

References [has\\_more\(\)](#), and [L4\\_UNLIKELY](#).

Here is the call graph for this function:



### 15.111.3.7 tag() [1/2]

```
l4\_msgtag\_t & L4::Ipc::Istream::tag () [inline]
```

Get the message tag of a received IPC.

#### Returns

A reference to the [L4](#) message tag for the received IPC.

This is in particular useful for handling page faults or exceptions.

See [operator>>\(\)](#)

Definition at line 517 of file [ipc\\_stream](#).

**15.111.3.8 tag()** [2/2]

```
l4_msgtag_t L4::Ipc::Istream::tag () const [inline]
```

Get the message tag of a received IPC.

**Returns**

The [L4](#) message tag for the received IPC.


This is in particular useful for handling page faults or exceptions.

See [operator>>\(\)](#)

Definition at line [505](#) of file [ipc\\_stream](#).

Referenced by [L4::lpc::lostream::call\(\)](#), [operator>>\(\)](#), [L4::lpc::lostream::reply\\_and\\_wait\(\)](#), and [wait\(\)](#).

Here is the caller graph for this function:

**15.111.3.9 wait()** [1/2]

```
l4_msgtag_t L4::Ipc::Istream::wait (
    l4_umword_t * src) [inline]
```

Wait for an incoming message from any sender.

**Parameters**

out	src	Contains the sender after a successful IPC operation.
-----	-----	---

### Returns

Syscall return tag.

This wait is actually known as 'open wait'.

Definition at line 548 of file [ipc\\_stream](#).

References [L4\\_IPC\\_NEVER](#), and [wait\(\)](#).

Referenced by [wait\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



#### 15.111.3.10 wait() [2/2]

```
l4_msgtag_t L4::Ipc::Istream::wait (  
    l4_unword_t * src,  
    l4_timeout_t timeout) [inline]
```

Wait for an incoming message from any sender.

### Parameters

out	src	Contains the sender after a successful IPC operation.
	timeout	Timeout used for IPC.

## Returns


The IPC result tag ([l4\\_msgtag\\_t](#)).

This wait is actually known as 'open wait'.

Definition at line 1013 of file [ipc\\_stream](#).

References [l4\\_ipc\\_wait\(\)](#), and [tag\(\)](#).

Here is the call graph for this function:




The documentation for this class was generated from the following file:

- [l4/cxx/ipc\\_stream](#)

## 15.112 L4::ipc::Msg::Cnt\_val\_ops< MTYPE, DIR, CLASS > Struct Template Reference


Defines client-side handling of 'MTYPE' as RPC argument.

Inheritance diagram for `L4::ipc::Msg::Cnt_val_ops< MTYPE, DIR, CLASS >`:





Collaboration diagram for L4::lpc::Msg::Cnt\_val\_ops< MTYPE, DIR, CLASS >:



### 15.112.1 Detailed Description

```
template<typename MTYPE, typename DIR, typename CLASS>
struct L4::lpc::Msg::Cnt_val_ops< MTYPE, DIR, CLASS >
```

Defines client-side handling of 'MTYPE' as RPC argument.

#### Template Parameters

<i>MTYPE</i>	Elem<T>::arg_type (where T is the type used in the RPC definition)
<i>DIR</i>	<a href="#">Dir_in</a> (client -> server), or <a href="#">Dir_out</a> (server -> client)
<i>CLASS</i>	<a href="#">Cls_data</a> , <a href="#">Cls_item</a> , or <a href="#">Cls_buffer</a>

Definition at line 210 of file [ipc\\_basics](#).

The documentation for this struct was generated from the following file:


- `l4/sys/cxx/ipc_basics`

## 15.113 L4::lpc::Msg::Cls\_buffer Struct Reference


Marker type for receive buffer values.

```
#include <ipc_basics>
```

Inheritance diagram for L4::lpc::Msg::Cls\_buffer:



Collaboration diagram for L4::lpc::Msg::Cls\_buffer:



### 15.113.1 Detailed Description

Marker type for receive buffer values.

Definition at line 154 of file [ipc\\_basics](#).

The documentation for this struct was generated from the following file:


- `l4/sys/cxx/ipc_basics`

## 15.114 L4::lpc::Msg::Cls\_data Struct Reference


Marker type for data values.

```
#include <ipc_basics>
```

Inheritance diagram for L4::lpc::Msg::Cls\_data:



Collaboration diagram for L4::lpc::Msg::Cls\_data:



### 15.114.1 Detailed Description

Marker type for data values.

Definition at line 150 of file [ipc\\_basics](#).

The documentation for this struct was generated from the following file:


- `l4/sys/cxx/ipc_basics`

## 15.115 L4::lpc::Msg::Cls\_item Struct Reference


Marker type for item values.

```
#include <ipc_basics>
```

Inheritance diagram for L4::lpc::Msg::Cls\_item:



Collaboration diagram for L4::lpc::Msg::Cls\_item:



### 15.115.1 Detailed Description

Marker type for item values.

Definition at line 152 of file [ipc\\_basics](#).

The documentation for this struct was generated from the following file:


- l4/sys/cxx/ipc\_basics

## 15.116 L4::lpc::Msg::Dir\_in Struct Reference


Marker type for input values.

```
#include <ipc_basics>
```

Inheritance diagram for L4::lpc::Msg::Dir\_in:



Collaboration diagram for L4::lpc::Msg::Dir\_in:



### 15.116.1 Detailed Description

Marker type for input values.

Definition at line [145](#) of file [ipc\\_basics](#).

The documentation for this struct was generated from the following file:


- `l4/sys/cxx/ipc_basics`

## 15.117 L4::lpc::Msg::Dir\_out Struct Reference


Marker type for output values.

```
#include <ipc_basics>
```

Inheritance diagram for L4::lpc::Msg::Dir\_out:



Collaboration diagram for L4::lpc::Msg::Dir\_out:



### 15.117.1 Detailed Description

Marker type for output values.

Definition at line 147 of file [ipc\\_basics](#).

The documentation for this struct was generated from the following file:


- `l4/sys/cxx/ipc_basics`

## 15.118 L4::lpc::Msg::Do\_in\_data Struct Reference


Marker for Input data.

```
#include <ipc_basics>
```

Inheritance diagram for L4::lpc::Msg::Do\_in\_data:



Collaboration diagram for L4::lpc::Msg::Do\_in\_data:



### 15.118.1 Detailed Description

Marker for Input data.

Definition at line 158 of file `ipc_basics`.

The documentation for this struct was generated from the following file:


- `l4/sys/cxx/ipc_basics`

## 15.119 L4::lpc::Msg::Do\_in\_items Struct Reference


Marker for Input items.

```
#include <ipc_basics>
```

Inheritance diagram for L4::lpc::Msg::Do\_in\_items:



Collaboration diagram for L4::lpc::Msg::Do\_in\_items:





### 15.119.1 Detailed Description

Marker for Input items.

Definition at line 162 of file [ipc\\_basics](#).

The documentation for this struct was generated from the following file:


- l4/sys/cxx/ipc\_basics

## 15.120 L4::lpc::Msg::Do\_out\_data Struct Reference


Marker for Output data.

```
#include <ipc_basics>
```

Inheritance diagram for L4::lpc::Msg::Do\_out\_data:



Collaboration diagram for L4::lpc::Msg::Do\_out\_data:



### 15.120.1 Detailed Description

Marker for Output data.

Definition at line 160 of file [ipc\\_basics](#).

The documentation for this struct was generated from the following file:


- `l4/sys/cxx/ipc_basics`

## 15.121 L4::lpc::Msg::Do\_out\_items Struct Reference


Marker for Output items.

```
#include <ipc_basics>
```

Inheritance diagram for L4::lpc::Msg::Do\_out\_items:



Collaboration diagram for L4::lpc::Msg::Do\_out\_items:



### 15.121.1 Detailed Description

Marker for Output items.

Definition at line 164 of file [ipc\\_basics](#).

The documentation for this struct was generated from the following file:


- `I4/sys/cxx/ipc_basics`

## 15.122 L4::lpc::Msg::Do\_rcv\_buffers Struct Reference


Marker for receive buffers.

```
#include <ipc_basics>
```

Inheritance diagram for L4::lpc::Msg::Do\_rcv\_buffers:



Collaboration diagram for L4::lpc::Msg::Do\_rcv\_buffers:



### 15.122.1 Detailed Description

Marker for receive buffers.

Definition at line 166 of file [ipc\\_basics](#).

The documentation for this struct was generated from the following file:


- l4/sys/cxx/ipc\_basics

## 15.123 L4::lpc::Msg::Elem< Array< A, LEN > & > Struct Template Reference

[Array](#) as output argument.

```
#include <ipc_array>
```

Collaboration diagram for L4::lpc::Msg::Elem< Array< A, LEN > & >:



### Public Types

- typedef [Array](#)< A, LEN > & **arg\_type**  
*[Array](#)<> & at the interface.*
- typedef [Array\\_ref](#)< A, LEN > **svr\_type**  
*[Array\\_ref](#)<> as server storage type.*
- typedef [svr\\_type](#) & **svr\_arg\_type**  
*[Array\\_ref](#)<> & at the server side.*

### 15.123.1 Detailed Description

```
template<typename A, typename LEN>
struct L4::lpc::Msg::Elem< Array< A, LEN > & >
```

[Array](#) as output argument.

Definition at line 170 of file [ipc\\_array](#).

The documentation for this struct was generated from the following file:


- l4/sys/cxx/ipc\_array

## 15.124 L4::lpc::Msg::Elem< Array< A, LEN > > Struct Template Reference

[Array](#) as input arguments.

```
#include <ipc_array>
```

Collaboration diagram for L4::lpc::Msg::Elem< Array< A, LEN > >:



### Public Types

- typedef [Array](#)< A, LEN > **arg\_type**  
[Array](#)<> as argument at the interface.
- typedef [Array\\_ref](#)< A, LEN > **svr\_type**  
[Array\\_ref](#)<> at the server side.

### 15.124.1 Detailed Description

```
template<typename A, typename LEN>
struct L4::lpc::Msg::Elem< Array< A, LEN > >
```

[Array](#) as input arguments.

Definition at line 158 of file [ipc\\_array](#).

The documentation for this struct was generated from the following file:


- l4/sys/cxx/ipc\_array

## 15.125 L4::lpc::Msg::Elem< Array\_ref< A, LEN > & > Struct Template Reference

[Array\\_ref](#) as output argument.

```
#include <ipc_array>
```

Collaboration diagram for L4::lpc::Msg::Elem< Array\_ref< A, LEN > & >:



### Public Types

- typedef [Array\\_ref](#)< A, LEN > & **arg\_type**  
*[Array\\_ref](#)<> at the interface.*
- typedef [Array\\_ref](#)< typename L4::Types::Remove\_const< A >::type, LEN > **svr\_type**  
*[Array\\_ref](#)<> as server storage.*
- typedef [svr\\_type](#) & **svr\_arg\_type**  
*[Array\\_ref](#)<> & as server argument.*

### 15.125.1 Detailed Description

```
template<typename A, typename LEN>
struct L4::lpc::Msg::Elem< Array_ref< A, LEN > & >
```

[Array\\_ref](#) as output argument.

Definition at line 183 of file [ipc\\_array](#).

The documentation for this struct was generated from the following file:


- l4/sys/cxx/ipc\_array

## 15.126 L4::lpc::Msg::False Struct Reference

[False](#) meta value.


```
#include <types>
```

Inheritance diagram for L4::lpc::Msg::False:





Collaboration diagram for L4::lpc::Msg::False:



#### Additional Inherited Members

#### Public Types inherited from `L4::Types::Bool< false >`

- typedef `Bool< V >` **type**  
*The meta type itself.*

#### 15.126.1 Detailed Description

`False` meta value.

Definition at line 317 of file `types`.

The documentation for this struct was generated from the following file:


- `l4/sys/cxx/types`

## 15.127 L4::lpc::Msg::ls\_valid\_rpc\_type< T > Struct Template Reference


Type trait defining a valid RPC parameter type.

```
#include <ipc_basics>
```

Inheritance diagram for L4::lpc::Msg::ls\_valid\_rpc\_type< T >:



Collaboration diagram for L4::lpc::Msg::ls\_valid\_rpc\_type< T >:



#### Additional Inherited Members

#### Public Types inherited from `L4::Types::Bool< true >`

- typedef `Bool< V > type`  
The meta type itself.

#### 15.127.1 Detailed Description

```
template<typename T>
struct L4::lpc::Msg::ls_valid_rpc_type< T >
```

Type trait defining a valid RPC parameter type.

Definition at line 339 of file `ipc_basics`.


The documentation for this struct was generated from the following file:

- `l4/sys/cxx/ipc_basics`

## 15.128 L4::lpc::Msg::Svr\_arg\_pack< IPC\_TYPE > Struct Template Reference

Server-side RPC arguments data structure used to provide arguments to the server-side implementation of an RPC function.

Collaboration diagram for L4::lpc::Msg::Svr\_arg\_pack< IPC\_TYPE >:



### 15.128.1 Detailed Description

```
template<typename IPC_TYPE>
struct L4::lpc::Msg::Svr_arg_pack< IPC_TYPE >
```

Server-side RPC arguments data structure used to provide arguments to the server-side implementation of an RPC function.

Definition at line 183 of file [ipc\\_server](#).


The documentation for this struct was generated from the following file:

- l4/sys/cxx/ipc\_server


## 15.129 L4::lpc::Msg::Svr\_val\_ops< MTYPE, DIR, CLASS > Struct Template Reference

Defines server-side handling for MTYPE server arguments.

Inheritance diagram for L4::lpc::Msg::Svr\_val\_ops< MTYPE, DIR, CLASS >:



Collaboration diagram for L4::lpc::Msg::Svr\_val\_ops< MTYPE, DIR, CLASS >:



### 15.129.1 Detailed Description

```
template<typename MTYPE, typename DIR, typename CLASS>
struct L4::lpc::Msg::Svr_val_ops< MTYPE, DIR, CLASS >
```

Defines server-side handling for `MTYPE` server arguments.

#### Template Parameters

<i>MTYPE</i>	Elem<T>::svr_type (where T is the type used in the RPC definition)
<i>DIR</i>	<a href="#">Dir_in</a> (client -> server), or <a href="#">Dir_out</a> (server -> client)
<i>CLASS</i>	<a href="#">Cls_data</a> , <a href="#">Cls_item</a> , or <a href="#">Cls_buffer</a>

Definition at line [264](#) of file [ipc\\_basics](#).

The documentation for this struct was generated from the following file:


- `I4/sys/cxx/ipc_basics`

## 15.130 L4::lpc::Msg::True Struct Reference


[True](#) meta value.

```
#include <types>
```

Inheritance diagram for L4::lpc::Msg::True:



Collaboration diagram for L4::lpc::Msg::True:



#### Additional Inherited Members

#### Public Types inherited from `L4::Types::Bool< true >`

- typedef `Bool< V >` **type**  
*The meta type itself.*

#### 15.130.1 Detailed Description

`True` meta value.

Definition at line 321 of file `types`.

The documentation for this struct was generated from the following file:


- `l4/sys/cxx/types`

## 15.131 L4::lpc::Msg\_ptr< T > Class Template Reference

Pointer to an element of type T in an [lpc::lstream](#).

```
#include <ipc_stream>
```

Collaboration diagram for L4::lpc::Msg\_ptr< T >:



### Public Member Functions

- [Msg\\_ptr](#) (T \*&p)

Create a [Msg\\_ptr](#) object that set pointer *p* to point into the message buffer.

### 15.131.1 Detailed Description

```
template<typename T>
class L4::lpc::Msg_ptr< T >
```

Pointer to an element of type T in an [lpc::lstream](#).

This wrapper can be used to extract an element of type T from an [lpc::lstream](#), whereas the data is not copied out, but a pointer into the message buffer itself is returned. With is mechanism it is possible to avoid an extra copy of large data structures from a received IPC message, instead the returned pointer gives direct access to the data in the message.

See [msg\\_ptr\(\)](#).

Definition at line 229 of file [ipc\\_stream](#).



## 15.131.2 Constructor & Destructor Documentation

### 15.131.2.1 Msg\_ptr()

```
template<typename T>
L4::lpc::Msg_ptr< T >::Msg_ptr (
    T *& p) [inline], [explicit]
```

Create a [Msg\\_ptr](#) object that set pointer p to point into the message buffer.

#### Parameters

<i>p</i>	The pointer that is adjusted to point into the message buffer.
----------	--

Definition at line 240 of file [ipc\\_stream](#).

The documentation for this class was generated from the following file:


- [l4/cxx/ipc\\_stream](#)

## 15.132 L4::lpc::Opt< T > Struct Template Reference

Attribute for defining an optional RPC argument.

```
#include <ipc_types>
```

Inheritance diagram for L4::lpc::Opt< T >:



Collaboration diagram for L4::lpc::Opt< T >:

L4::lpc::Opt< T >
+ _value
+ _valid
+ Opt()
+ Opt()
+ operator=()
+ set_valid()
+ operator->()
+ operator->()
+ value()
+ value()
+ is_valid()

## Public Member Functions

- **Opt** () noexcept  
*Make an absent optional argument.*
- **Opt** (T [value](#)) noexcept  
*Make a present optional argument with the given value.*
- **Opt** & **operator=** (T [value](#)) noexcept  
*Assign a value to the optional argument (makes the argument present).*
- void **set\_valid** (bool valid=true) noexcept  
*Set the argument to present or absent.*
- T \* **operator->** () noexcept  
*Get the pointer to the value.*
- T const \* **operator->** () const noexcept  
*Get the const pointer to the value.*
- T **value** () const noexcept  
*Get the value.*
- T & **value** () noexcept  
*Get the value.*
- bool **is\_valid** () const noexcept  
*Get true if present, false if not.*

## Data Fields

- T **\_value**  
*The value.*
- bool **\_valid**  
*True if the optional argument is present, false else.*

### 15.132.1 Detailed Description

```
template<typename T>  
struct L4::lpc::Opt< T >
```

Attribute for defining an optional RPC argument.

Definition at line 136 of file [ipc\\_types](#).

The documentation for this struct was generated from the following file:


- [l4/sys/cxx/ipc\\_types](#)

## 15.133 L4::lpc::Ostream Class Reference


Output stream for IPC marshalling.

```
#include <ipc_stream>
```

Inheritance diagram for L4::lpc::Ostream:



Collaboration diagram for L4::lpc::Ostream:



## Public Member Functions

- **Ostream** ([l4\\_utcb\\_t](#) \*[utcb](#))  
Create an IPC output stream using the given message buffer [utcb](#).
- void **reset** ()  
Reset the stream to empty, same state as a newly created stream.
- [l4\\_utcb\\_t](#) \* **utcb** () const

*Return utcb pointer.*

### Get/Put functions.

*These functions are basically used to implement the insertion operators (<<) and should not be called directly.*

- `template<typename T>`  
`bool put (T *buf, unsigned long size)`  
*Put an array with `size` elements of type `T` into the stream.*
- `template<typename T>`  
`bool put (T const &v)`  
*Insert an element of type `T` into the stream.*
- `l4_msgtag_t tag () const`  
*Extract the `L4` message tag from the stream.*
- `l4_msgtag_t & tag ()`  
*Extract a reference to the `L4` message tag from the stream.*

### IPC operations.

- `l4_msgtag_t send (l4_cap_idx_t dst, long proto=0, unsigned flags=0)`  
*Send the message via IPC to the given receiver.*

## 15.133.1 Detailed Description

Output stream for IPC marshalling.

`lpc::Ostream` is part of the dynamic IPC marshalling infrastructure, as well as `lpc::Istream` and `lpc::lostream`.

`lpc::Ostream` is an output stream supporting insertion of values into an IPC message buffer. A IPC message can be marshalled using the usual insertion operator <<, see [IPC stream operators](#) .

There exist some special wrapper classes to insert arrays (see `lpc::Buf_cp_out`) and indirect strings (see `Msg_↔out_buffer` and `Msg_io_buffer`).

Definition at line 623 of file [ipc\\_stream](#).

## 15.133.2 Member Function Documentation

### 15.133.2.1 put() [1/2]

```
template<typename T>
bool L4::Ipc::Ostream::put (
    T * buf,
    unsigned long size) [inline]
```

Put an array with `size` elements of type `T` into the stream.


#### Parameters

<i>buf</i>	A pointer to the array to insert into the buffer.
<i>size</i>	The number of elements in the array.

Definition at line 660 of file [ipc\\_stream](#).

Referenced by [operator<<\(\)](#), [operator<<\(\)](#), and [operator<<\(\)](#).

Here is the caller graph for this function:



### 15.133.2.2 put() [2/2]

```
template<typename T>
bool L4::Ipc::Ostream::put (
    T const & v) [inline]
```

Insert an element of type T into the stream.

#### Parameters

<i>v</i>	The element to insert.
----------	------------------------

Definition at line 678 of file [ipc\\_stream](#).

### 15.133.2.3 send()

```
l4_msgtag_t L4::Ipc::Ostream::send (
    l4_cap_idx_t dst,
    long proto = 0,
    unsigned flags = 0) [inline]
```

Send the message via IPC to the given receiver.

#### Parameters

<i>dst</i>	The destination for the message.
<i>proto</i>	Protocol to use.

<i>flags</i>	Flags to use.
--------------	---------------


#### Returns

The syscall return tag.

Definition at line 959 of file [ipc\\_stream](#).

References [L4\\_IPC\\_NEVER](#), [l4\\_ipc\\_send\(\)](#), [L4\\_MSGTAG\\_FLAGS](#), and [tag\(\)](#).

Here is the call graph for this function:



#### 15.133.2.4 `tag()` [1/2]

```
l4_msgtag_t & L4::Ipcc::Ostream::tag () [inline]
```

Extract a reference to the [L4](#) message tag from the stream.

#### Returns

A reference to the [L4](#) message tag.

Definition at line 713 of file [ipc\\_stream](#).

#### 15.133.2.5 `tag()` [2/2]

```
l4_msgtag_t L4::Ipcc::Ostream::tag () const [inline]
```

Extract the [L4](#) message tag from the stream.




**Returns**

The extracted [L4](#) message tag.

Definition at line [706](#) of file [ipc\\_stream](#).

Referenced by [operator<<\(\)](#), and [send\(\)](#).

Here is the caller graph for this function:




The documentation for this class was generated from the following file:

- [l4/cxx/ipc\\_stream](#)

## 15.134 L4::lpc::Out< T > Struct Template Reference

Mark an argument as a output value in an RPC signature.

Collaboration diagram for L4::lpc::Out< T >:



### 15.134.1 Detailed Description

```
template<typename T>  
struct L4::lpc::Out< T >
```

Mark an argument as a output value in an RPC signature.

#### Template Parameters

<i>T</i>	The original type of the argument.
----------	------------------------------------

#### Note

The use of [Out<>](#) is usually not needed, because typical out-put data types in C++ (pointers to non-const objects or non-const references are interpreted as output values anyway. However, there are some data types, such as returned capabilities that can be marked as such by using [Out<>](#).

Definition at line 31 of file [ipc\\_types](#).

The documentation for this struct was generated from the following file:


- [l4/sys/cxx/ipc\\_types](#)

## 15.135 L4::lpc::Rcv\_fpage Class Reference


Non-small receive item.

```
#include <ipc_types>
```

Inheritance diagram for L4::lpc::Rcv\_fpage:



Collaboration diagram for L4::lpc::Rcv\_fpage:



## Public Member Functions

- **Rcv\_fpage** () noexcept  
*Construct a void receive item.*
- **Rcv\_fpage** (l4\_fpage\_t const &fp, l4\_addr\_t snd\_base=0, l4\_cap\_idx\_t rcv\_task=L4\_INVALID\_CAP) noexcept  
*Construct a non-small receive item.*
- **l4\_cap\_idx\_t rcv\_task** () const  
*Get the capability index of the destination task for received capabilities.*
- bool **forward\_mappings** () const noexcept  
*Check if rcv\_task() shall be used as destination for received capabilities.*

## Public Member Functions inherited from L4::lpc::Gen\_fpage

- **Gen\_fpage** (l4\_umword\_t base, l4\_umword\_t data) noexcept  
*Construct from raw values.*
- **l4\_umword\_t data** () const noexcept  
*Return the raw flexpage descriptor.*
- **l4\_umword\_t base\_x** () const noexcept  
*Return the raw base descriptor.*

## Static Public Member Functions

- static [Rcv\\_fpage obj](#) ([l4\\_cap\\_idx\\_t](#) base, int order, [l4\\_addr\\_t](#) snd\_base=0, [L4::Cap](#)< void > [rcv\\_task](#)=[L4::Cap](#)< void >::Invalid) noexcept  
*Construct a non-small receive item for the object space.*
- static [Rcv\\_fpage mem](#) ([l4\\_addr\\_t](#) base, int order, [l4\\_addr\\_t](#) snd\_base=0, [L4::Cap](#)< void > [rcv\\_task](#)=[L4::Cap](#)< void >::Invalid) noexcept  
*Construct a receive item for the memory space.*
- static [Rcv\\_fpage io](#) (unsigned long base, int order, [l4\\_addr\\_t](#) snd\_base=0, [L4::Cap](#)< void > [rcv\\_task](#)=[L4::Cap](#)< void >::Invalid) noexcept  
*Construct a receive item for the I/O port space.*

## Additional Inherited Members

## Public Types inherited from [L4::Ipc::Gen\\_fpage](#)

- enum [Type](#) { [Special](#) = L4\_FPAGE\_SPECIAL << 4 , [Memory](#) = L4\_FPAGE\_MEMORY << 4 , [Io](#) = L4\_FPAGE\_IO << 4 , [Obj](#) = L4\_FPAGE\_OBJ << 4 }
- Type of mapping object, see [L4\\_fpage\\_type](#).*

### 15.135.1 Detailed Description

Non-small receive item.

This class represents a non-small receive item. A receive item is a message item in the buffer registers of the UTCB of the receiver (see [l4\\_utcb\\_br\(\)](#)).

Definition at line 544 of file [ipc\\_types](#).

### 15.135.2 Constructor & Destructor Documentation

#### 15.135.2.1 [Rcv\\_fpage\(\)](#)

```
L4::Ipc::Rcv_fpage::Rcv_fpage (
    l4\_fpage\_t const & fp,
    l4\_addr\_t snd_base = 0,
    l4\_cap\_idx\_t rcv_task = L4_INVALID_CAP) [inline], [noexcept]
```

Construct a non-small receive item.


#### Parameters

<i>fp</i>	Flexpage defining where and which kind of capabilities may be received.
<i>snd_base</i>	Reserved; should be zero.
<i>rcv_task</i>	Optional destination task for received capabilities. If invalid, capabilities are received in the invoking task.

Definition at line 561 of file [ipc\\_types](#).

References [L4\\_INVALID\\_CAP](#), [L4\\_ITEM\\_MAP](#), [L4\\_RCV\\_ITEM\\_FORWARD\\_MAPPINGS](#), and [rcv\\_task\(\)](#).

Here is the call graph for this function:



### 15.135.3 Member Function Documentation

#### 15.135.3.1 io()

```

Rcv_fpage L4::Ipc::Rcv_fpage::io (
    unsigned long base,
    int order,
    l4_addr_t snd_base = 0,
    L4::Cap< void > rcv_task = L4::Cap<void>::Invalid) [inline], [static], [noexcept]
  
```

Construct a receive item for the I/O port space.


#### Parameters

<i>base</i>	Start of flexpage (see <a href="#">l4_iofpage()</a> ).
<i>order</i>	Log <sub>2</sub> size of flexpage (see <a href="#">l4_iofpage()</a> ).
<i>snd_base</i>	Reserved; should be zero.
<i>rcv_task</i>	Optional destination task for received capabilities. If invalid, capabilities are received in the invoking task.

Definition at line 609 of file [ipc\\_types](#).

References [L4::Cap\\_base::Invalid](#), [l4\\_iofpage\(\)](#), [Rcv\\_fpage\(\)](#), and [rcv\\_task\(\)](#).

Here is the call graph for this function:



### 15.135.3.2 mem()

```
Rcv_fpage L4::Ipc::Rcv_fpage::mem (
    l4_addr_t base,
    int order,
    l4_addr_t snd_base = 0,
    L4::Cap< void > rcv_task = L4::Cap<void>::Invalid) [inline], [static], [noexcept]
```

Construct a receive item for the memory space.

#### Parameters

<i>base</i>	Start of flexpage (see <a href="#">l4_fpage()</a> ).
<i>order</i>	Log <sub>2</sub> size of flexpage (see <a href="#">l4_fpage()</a> ).
<i>snd_base</i>	Reserved; should be zero.
<i>rcv_task</i>	Optional destination task for received capabilities. If invalid, capabilities are received in the invoking task.


#### Examples

[examples/libs/l4re/streammap/client.cc](#).

Definition at line 594 of file [ipc\\_types](#).

References [L4::Cap\\_base::Invalid](#), [l4\\_fpage\(\)](#), [Rcv\\_fpage\(\)](#), and [rcv\\_task\(\)](#).

Here is the call graph for this function:



### 15.135.3.3 obj()

```
Rcv_fpage L4::Ipc::Rcv_fpage::obj (
    l4_cap_idx_t base,
    int order,
    l4_addr_t snd_base = 0,
    L4::Cap< void > rcv_task = L4::Cap<void>::Invalid) [inline], [static], [noexcept]
```

Construct a non-small receive item for the object space.


#### Parameters

<i>base</i>	Start of flexpage (see <a href="#">l4_obj_fpage()</a> ).
<i>order</i>	$\log_2$ size of flexpage (see <a href="#">l4_obj_fpage()</a> ).
<i>snd_base</i>	Reserved; should be zero.
<i>rcv_task</i>	Optional destination task for received capabilities. If invalid, capabilities are received in the invoking task.

Definition at line 578 of file [ipc\\_types](#).

References [L4::Cap\\_base::Invalid](#), [l4\\_obj\\_fpage\(\)](#), [Rcv\\_fpage\(\)](#), and [rcv\\_task\(\)](#).

Here is the call graph for this function:



#### 15.135.3.4 rcv\_task()

```
l4_cap_idx_t L4::Ipc::Rcv_fpage::rcv_task () const [inline]
```


Get the capability index of the destination task for received capabilities.

Only relevant if [forward\\_mappings\(\)](#) is true.

Definition at line 620 of file [ipc\\_types](#).

Referenced by [io\(\)](#), [mem\(\)](#), [obj\(\)](#), and [Rcv\\_fpage\(\)](#).

Here is the caller graph for this function:





The documentation for this class was generated from the following file:


- [l4/sys/cxx/ipc\\_types](#)

## 15.136 L4::lpc::Ret\_array< T > Struct Template Reference


Dynamically sized output array of type T.

```
#include <ipc_ret_array>
```

Inheritance diagram for L4::lpc::Ret\_array< T >:



Collaboration diagram for L4::lpc::Ret\_array< T >:



### 15.136.1 Detailed Description

```
template<typename T>
struct L4::lpc::Ret_array< T >
```

Dynamically sized output array of type T.

#### Template Parameters

<i>T</i>	The data-type of each array element.
----------	--------------------------------------

[Ret\\_array<>](#) is a special dynamically sized output array where the number of transmitted elements is passed in the return value of the call (if positive)

Definition at line 23 of file [ipc\\_ret\\_array](#).

The documentation for this struct was generated from the following file:


- [l4/sys/cxx/ipc\\_ret\\_array](#)

## 15.137 L4::lpc::Send\_only Struct Reference

RPC attribute for a send-only RPC.

```
#include <ipc_iface>
```

Collaboration diagram for L4::lpc::Send\_only:



### 15.137.1 Detailed Description

RPC attribute for a send-only RPC.

This class can be used as FLAGS parameter to [L4::lpc::Msg::Rpc\\_call](#) and [L4::lpc::Msg::Rpc\\_inline\\_call](#) templates and declares the RPC to use send-only semantics and timeouts.

Examples:

```
L4\_RPC\(l4\_ret\_t, send, \(unsigned value\), L4::lpc::Send\_only\);
```

Definition at line 287 of file [ipc\\_iface](#).

The documentation for this struct was generated from the following file:


- [l4/sys/cxx/ipc\\_iface](#)

## 15.138 L4::lpc::Small\_buf Class Reference

A receive item for receiving a single object capability.

```
#include <ipc_types>
```

Collaboration diagram for L4::lpc::Small\_buf:



### Public Member Functions

- [Small\\_buf](#) ([L4::Cap](#)< void > cap, unsigned long flags=0) noexcept  
*Create a receive item from a C++ cap.*
- [Small\\_buf](#) ([l4\\_cap\\_idx\\_t](#) cap, unsigned long flags=0) noexcept  
*Create a receive item from a C cap.*
- [l4\\_umword\\_t raw](#) () const noexcept  
*Return the raw data.*

### 15.138.1 Detailed Description

A receive item for receiving a single object capability.

This class is the main abstraction for receiving object capabilities via [lpc::lstream](#). To receive an object capability, an instance of [Small\\_buf](#) that refers to an empty capability slot must be inserted into the [lpc::lstream](#) before the receive operation.

Definition at line 257 of file [ipc\\_types](#).

## 15.138.2 Constructor & Destructor Documentation

### 15.138.2.1 Small\_buf() [1/2]

```
L4::Ipc::Small_buf::Small_buf (
    L4::Cap< void > cap,
    unsigned long flags = 0) [inline], [explicit], [noexcept]
```

Create a receive item from a C++ cap.

#### Parameters

<i>cap</i>	Capability slot where to save the capability.
<i>flags</i>	Receive buffer flags, see <a href="#">l4_msg_item_consts_t</a> . <a href="#">L4_RCV_ITEM_SINGLE_CAP</a> will always be set.

Definition at line 267 of file [ipc\\_types](#).

References [L4\\_RCV\\_ITEM\\_SINGLE\\_CAP](#).

### 15.138.2.2 Small\_buf() [2/2]

```
L4::Ipc::Small_buf::Small_buf (
    l4_cap_idx_t cap,
    unsigned long flags = 0) [inline], [explicit], [noexcept]
```

Create a receive item from a C cap.

#### Parameters

<i>cap</i>	Capability slot where to save the capability.
<i>flags</i>	Receive buffer flags, see <a href="#">l4_msg_item_consts_t</a> . <a href="#">L4_RCV_ITEM_SINGLE_CAP</a> will always be set.

Definition at line 274 of file [ipc\\_types](#).

References [L4\\_RCV\\_ITEM\\_SINGLE\\_CAP](#).

The documentation for this class was generated from the following file:


- [l4/sys/cxx/ipc\\_types](#)

## 15.139 L4::lpc::Snd\_fpage Class Reference


Send item or return item.

```
#include <ipc_types>
```

Inheritance diagram for L4::lpc::Snd\_fpage:



Collaboration diagram for L4::lpc::Snd\_fpage:



## Public Types

- enum [Map\\_type](#) { [Map](#) = L4\_MAP\_ITEM\_MAP , [Grant](#) = L4\_MAP\_ITEM\_GRANT }  
(Defined for send items only.) Kind of mapping.
- enum [Cacheopt](#) { [None](#) = 0 , [Cached](#) = L4\_FPAGE\_CACHEABLE << 4 , [Buffered](#) = L4\_FPAGE\_BUFFERABLE << 4 , [Uncached](#) = L4\_FPAGE\_UNCACHEABLE << 4 }  
(Defined for memory send items only.) Caching options, see [l4\\_fpage\\_cacheability\\_opt\\_t](#).
- enum [Continue](#) { [Single](#) = 0 , [Last](#) = 0 , [More](#) = L4\_ITEM\_CONT , [Compound](#) = L4\_ITEM\_CONT }  
Specify if the following item is associated with the same receive item as this one, see [L4\\_ITEM\\_CONT](#).

## Public Types inherited from L4::lpc::Gen\_fpage

- enum [Type](#) { [Special](#) = L4\_FPAGE\_SPECIAL << 4 , [Memory](#) = L4\_FPAGE\_MEMORY << 4 , [Io](#) = L4\_FPAGE\_IO << 4 , [Obj](#) = L4\_FPAGE\_OBJ << 4 }

*Type of mapping object, see [L4\\_fpage\\_type](#).*

## Public Member Functions

- [Snd\\_fpage](#) ([l4\\_umword\\_t](#) base=0, [l4\\_umword\\_t](#) data=0) noexcept  
*Construct from raw values.*
- [Snd\\_fpage](#) ([l4\\_fpage\\_t](#) const &fp, [l4\\_addr\\_t](#) snd\_base=0, [Map\\_type](#) map\_type=[Map](#), [Cacheopt](#) cache=[None](#), [Continue](#) cont=[Last](#)) noexcept  
*Construct a send item for the memory space.*
- [Snd\\_fpage](#) ([L4::Cap](#)< void > cap, unsigned rights, [Map\\_type](#) map\_type=[Map](#)) noexcept  
*Construct a send item for the object space.*
- unsigned [order](#) () const noexcept  
*(Defined only if send item or if [local\\_id\\_received\(\)](#) is true.) Get log<sub>2</sub> size.*
- unsigned [snd\\_order](#) () const noexcept  
*(Defined only if send item or if [local\\_id\\_received\(\)](#) is true.) Get log<sub>2</sub> size.*
- unsigned [rcv\\_order](#) () const noexcept  
*(Defined for return items only.) Get log<sub>2</sub> size.*
- [l4\\_addr\\_t](#) [base](#) () const noexcept  
*(Defined only if send item or if [local\\_id\\_received\(\)](#) is true.) Get the start of the item (i.e., the start of its flexpage).*
- [l4\\_addr\\_t](#) [snd\\_base](#) () const noexcept  
*Get the position in receive window for the case that this item has a different size than the corresponding receive item.*
- void [snd\\_base](#) ([l4\\_addr\\_t](#) b) noexcept  
*Set the position in receive window for the case that this item has a different size than the corresponding receive item.*
- bool [is\\_valid](#) () const noexcept  
*Check if the capability is valid.*
- bool [cap\\_received](#) () const noexcept  
*(Defined for return items only.) Check if at least one object capability has been mapped for this item.*
- bool [id\\_received](#) () const noexcept  
*(Defined for return items only.) Check if an IPC gate label has been received instead of a mapping.*
- bool [local\\_id\\_received](#) () const noexcept  
*(Defined for return items only.) Check if a raw object flexpage has been received instead of a mapping.*
- bool [is\\_compound](#) () const noexcept  
*Check if the item has the compound bit set, see [Continue](#).*

## Public Member Functions inherited from L4::lpc::Gen\_fpage

- [Gen\\_fpage](#) ([l4\\_umword\\_t](#) base, [l4\\_umword\\_t](#) data) noexcept  
*Construct from raw values.*
- [l4\\_umword\\_t](#) [data](#) () const noexcept  
*Return the raw flexpage descriptor.*
- [l4\\_umword\\_t](#) [base\\_x](#) () const noexcept  
*Return the raw base descriptor.*

## Static Public Member Functions

- static [Snd\\_fpage obj](#) ([l4\\_cap\\_idx\\_t](#) base, int [order](#), unsigned char rights, [l4\\_addr\\_t](#) snd\_base=0, [Map\\_type](#) map\_type=[Map](#), [Continue](#) cont=[Last](#)) noexcept  
Construct a send item for the object space.
- static [Snd\\_fpage mem](#) ([l4\\_addr\\_t](#) base, int [order](#), unsigned char rights, [l4\\_addr\\_t](#) snd\_base=0, [Map\\_type](#) map\_type=[Map](#), [Cacheopt](#) cache=[None](#), [Continue](#) cont=[Last](#)) noexcept  
Construct a send item for the memory space.
- static [Snd\\_fpage io](#) (unsigned long base, int [order](#), unsigned char rights, [l4\\_addr\\_t](#) snd\_base=0, [Map\\_type](#) map\_type=[Map](#), [Continue](#) cont=[Last](#)) noexcept  
Construct a send item for the I/O port space.

### 15.139.1 Detailed Description

Send item or return item.

This class represents a typed message item in the message registers of the UTCB. If it is provided by the sender, then it is a *send item*. If it is provided by the kernel during IPC, it is a *return item*.

Note that some members are dedicated for send items only or return items only.

Definition at line 323 of file [ipc\\_types](#).

### 15.139.2 Member Enumeration Documentation

#### 15.139.2.1 Cacheopt

enum [L4::Ipc::Snd\\_fpage::Cacheopt](#)

(Defined for memory send items only.) Caching options, see [l4\\_fpage\\_cacheability\\_opt\\_t](#).

#### Enumerator

None	Copy options from sender.
Cached	Cacheability option to enable caches for the mapping.
Buffered	Cacheability option to enable buffered writes for the mapping.
Uncached	Cacheability option to disable caching for the mapping.

Definition at line 336 of file [ipc\\_types](#).



### 15.139.2.2 Continue

```
enum L4::Ipc::Snd_fpage::Continue
```

Specify if the following item is associated with the same receive item as this one, see [L4\\_ITEM\\_CONT](#).

#### Enumerator

Single	Inverse of <a href="#">Compound</a> .
Last	Inverse of <a href="#">More</a> .
More	Alias for <a href="#">Compound</a> .
Compound	Denote that the following item shall be put into the same receive item as this one.

Definition at line 346 of file [ipc\\_types](#).

### 15.139.2.3 Map\_type

```
enum L4::Ipc::Snd_fpage::Map_type
```

(Defined for send items only.) Kind of mapping.

#### Enumerator

Map	Flag as usual <i>map</i> operation.
Grant	<p>Flag as <i>grant</i> instead of <i>map</i> operation. This means, the sender delegates access to the receiver and the kernel removes the rights from the sender (basically a move operation). The mapping in the receiver gets the new parent of any child mappings of the mapping of the sender. Rights revocation via send item/flexpage is <i>not</i> guaranteed to be applied to descendant mappings in case of grant. See <a href="#">Spaces and Mappings</a> for more details on map/grant.</p> <p><b>Note</b></p> <p>The grant operation is not performed if the resulting rights of the receiver mapping would not contain the <a href="#">L4_CAP_FPAGE_R</a> bit (for object capabilities) or none of the <a href="#">L4_FPAGE_RWX</a> bits (memory and IO ports). In that case, the mapping is not created in the receiver space and not removed from the sender space.</p> <p>If the removal of the whole mapping from the sender is not possible because the size of the mapped frame at the sender exceeds the size defined by the send or receive flexpage, the grant operation is turned into a regular map operation and the mapping is <i>not</i> removed from the sender. This would happen if, for example, a smaller part of an <a href="#">L4</a> superpage mapping shall be granted.</p>

Definition at line 328 of file [ipc\\_types](#).

## 15.139.3 Constructor & Destructor Documentation

### 15.139.3.1 Snd\_fpage() [1/2]

```
L4::Ipc::Snd_fpage::Snd_fpage (
    l4_fpage_t const & fp,
```

```

l4_addr_t snd_base = 0,
Map_type map_type = Map,
Cacheopt cache = None,
Continue cont = Last) [inline], [noexcept]

```

Construct a send item for the memory space.


#### Parameters

<i>fp</i>	Memory flexpage defining which range and kind of capabilities shall be sent (see <a href="#">l4_fpage()</a> ).
<i>snd_base</i>	Position in receive window in case it has a different size than <i>fp</i> .
<i>map_type</i>	See <a href="#">Map_type</a> .
<i>cache</i>	See <a href="#">Cacheopt</a> .
<i>cont</i>	See <a href="#">Continue</a> .

Definition at line 370 of file [ipc\\_types](#).

References [L4\\_ITEM\\_MAP](#), [Last](#), [Map](#), [None](#), and [snd\\_base\(\)](#).

Here is the call graph for this function:



#### 15.139.3.2 Snd\_fpage() [2/2]

```

L4::Ipc::Snd_fpage::Snd_fpage (
    L4::Cap< void > cap,
    unsigned rights,
    Map_type map_type = Map) [inline], [noexcept]

```

Construct a send item for the object space.

#### Parameters

<i>cap</i>	Capability to be sent.
<i>rights</i>	Permissions to be transferred. See <a href="#">L4_cap_fpage_rights</a> and <a href="#">Attributes and additional permissions for object send items</a> .
<i>map_type</i>	See <a href="#">Map_type</a> .

Definition at line 386 of file [ipc\\_types](#).

References [L4\\_ITEM\\_MAP](#), and [Map](#).

## 15.139.4 Member Function Documentation

### 15.139.4.1 cap\_received()

```
bool L4::Ipc::Snd_fpage::cap_received () const [inline], [noexcept]
```

(*Defined for return items only.*) Check if at least one object capability has been mapped for this item.

The capabilities themselves can then be retrieved from the cap slots that have been provided in the receive operation.

#### Note

If this function returns `true` and the receive window covers more than one capability slot, then it is not possible to determine which slots actually got capabilities mapped from the sender.

If the received capabilities do not have type object (see [L4\\_FPAGE\\_OBJ](#)), then this function returns `false`.

Definition at line 496 of file [ipc\\_types](#).

### 15.139.4.2 id\_received()

```
bool L4::Ipc::Snd_fpage::id_received () const [inline], [noexcept]
```

(*Defined for return items only.*) Check if an IPC gate label has been received instead of a mapping.

If the [L4\\_RCV\\_ITEM\\_LOCAL\\_ID](#) flag has been set by the receiver, the conditions for [local\\_id\\_received\(\)](#) do not apply, the sender sent an IPC gate capability, and the receiving thread is in the same task as the thread that is attached to the IPC gate, then no mapping is done for this item and only the bitwise OR (`|`) of the label of the IPC gate and the special and write permission ([L4\\_CAP\\_FPAGE\\_S](#) and [L4\\_CAP\\_FPAGE\\_W](#)) that would have been mapped is received.

The bitwise OR of the label and the permissions can be retrieved with [Gen\\_fpage::data\(\)](#).

Definition at line 512 of file [ipc\\_types](#).

### 15.139.4.3 io()

```
Snd_fpage L4::Ipc::Snd_fpage::io (
    unsigned long base,
    int order,
    unsigned char rights,
    l4_addr_t snd_base = 0,
    Map_type map_type = Map,
    Continue cont = Last) [inline], [static], [noexcept]
```

Construct a send item for the I/O port space.

#### Parameters


<i>base</i>	Start of flexpage (see <a href="#">l4_iofpage()</a> ).
-------------	--

<i>order</i>	Log <sub>2</sub> size of flexpage (see <a href="#">l4_iofpage()</a> ).
<i>rights</i>	Permissions of flexpage (see <a href="#">L4_fpage_rights</a> ).
<i>snd_base</i>	Position in receive window in case it has a different size than 1 << <a href="#">order</a> .
<i>map_type</i>	See <a href="#">Map_type</a> .
<i>cont</i>	See <a href="#">Continue</a> .

Definition at line 445 of file [ipc\\_types](#).

References [base\(\)](#), [l4\\_fpage\\_set\\_rights\(\)](#), [l4\\_iofpage\(\)](#), [Last](#), [Map](#), [None](#), [order\(\)](#), [snd\\_base\(\)](#), and [Snd\\_fpage\(\)](#).

Here is the call graph for this function:



#### 15.139.4.4 is\_compound()

```
bool L4::Ipc::Snd_fpage::is_compound () const [inline], [noexcept]
```

Check if the item has the compound bit set, see [Continue](#).

A set compound bit means the next message item of the same type will be mapped to the same receive buffer as this message item.

Definition at line 535 of file [ipc\\_types](#).

#### 15.139.4.5 local\_id\_received()

```
bool L4::Ipc::Snd_fpage::local_id_received () const [inline], [noexcept]
```

(Defined for return items only.) Check if a raw object flexpage has been received instead of a mapping.

If the [L4\\_RCV\\_ITEM\\_LOCAL\\_ID](#) flag has been set by the receiver, and sender and receiver are in the same task, then no mapping is done for this item and only the raw flexpage ([l4\\_fpage\\_t](#)) is received.

This function checks if this is the case and if it is an object flexpage.

The flexpage can be retrieved with [Gen\\_fpage::data\(\)](#).

#### Note

If a raw flexpage was received, but it does not have type object (see [L4\\_FPAGE\\_OBJ](#)), then this function returns `false`.

Definition at line 528 of file [ipc\\_types](#).

## 15.139.4.6 mem()

```
Snd_fpage L4::Ipc::Snd_fpage::mem (
    l4_addr_t base,
    int order,
    unsigned char rights,
    l4_addr_t snd_base = 0,
    Map_type map_type = Map,
    Cacheopt cache = None,
    Continue cont = Last) [inline], [static], [noexcept]
```

Construct a send item for the memory space.

## Parameters

<i>base</i>	Start of flexpage (see <a href="#">l4_fpage()</a> ).
<i>order</i>	Log <sub>2</sub> size of flexpage (see <a href="#">l4_fpage()</a> ).
<i>rights</i>	Permissions of flexpage (see <a href="#">l4_fpage()</a> ).
<i>snd_base</i>	Position in receive window in case it has a different size than 1 << <a href="#">order</a> .
<i>map_type</i>	See <a href="#">Map_type</a> .
<i>cache</i>	See <a href="#">Cacheopt</a> .
<i>cont</i>	See <a href="#">Continue</a> .


## Examples

[examples/libs/l4re/streammap/server.cc](#).

Definition at line 424 of file [ipc\\_types](#).

References [base\(\)](#), [l4\\_fpage\(\)](#), [Last](#), [Map](#), [None](#), [order\(\)](#), [snd\\_base\(\)](#), and [Snd\\_fpage\(\)](#).

Here is the call graph for this function:



### 15.139.4.7 obj()

```
Snd_fpage L4::Ipc::Snd_fpage::obj (
    l4_cap_idx_t base,
    int order,
    unsigned char rights,
    l4_addr_t snd_base = 0,
    Map_type map_type = Map,
    Continue cont = Last) [inline], [static], [noexcept]
```

Construct a send item for the object space.


#### Parameters

<i>base</i>	Start of flexpage (see <a href="#">l4_obj_fpage()</a> ).
<i>order</i>	$\log_2$ size of flexpage (see <a href="#">l4_obj_fpage()</a> ).
<i>rights</i>	Permissions of flexpage (see <a href="#">l4_obj_fpage()</a> ).
<i>snd_base</i>	Position in receive window in case it has a different size than $1 \ll order$ .
<i>map_type</i>	See <a href="#">Map_type</a> .
<i>cont</i>	See <a href="#">Continue</a> .

Definition at line 402 of file [ipc\\_types](#).

References [base\(\)](#), [l4\\_obj\\_fpage\(\)](#), [Last](#), [Map](#), [None](#), [order\(\)](#), [snd\\_base\(\)](#), and [Snd\\_fpage\(\)](#).

Here is the call graph for this function:



The documentation for this class was generated from the following file:


- [l4/sys/cxx/ipc\\_types](#)

## 15.140 L4::lpc::Str\_cp\_in< T > Class Template Reference

Abstraction for extracting a zero-terminated string from an [lpc::lstream](#).

```
#include <ipc_stream>
```

Collaboration diagram for L4::lpc::Str\_cp\_in< T >:



### Public Member Functions

- [Str\\_cp\\_in](#) (T \*v, unsigned long &size)  
Create a buffer for extracting an array from an [lpc::lstream](#).

### 15.140.1 Detailed Description

```
template<typename T>
class L4::lpc::Str_cp_in< T >
```

Abstraction for extracting a zero-terminated string from an [lpc::lstream](#).

An instance of [Str\\_cp\\_in](#) can be used to extract a zero-terminated string an [lpc::lstream](#). The data from the received message is thereby copied to the given buffer and size is set to the number of characters found in the stream. The string is zero terminated in any circumstances. When the given buffer is smaller than the received string the last byte in the buffer will be the zero terminator. In the case the received string is shorter than the given buffer the zero termination will be placed behind the received data. This provides a zero-terminated result even in cases where the sender did not provide proper termination or in cases of too small receiver buffers.

See also

[str\\_cp\\_in\(\)](#).

Definition at line 178 of file [ipc\\_stream](#).

## 15.140.2 Constructor & Destructor Documentation

### 15.140.2.1 Str\_cp\_in()

```
template<typename T>
L4::Ipc::Str_cp_in< T >::Str_cp_in (
    T * v,
    unsigned long & size) [inline]
```

Create a buffer for extracting an array from an [lpc::lstream](#).

#### Parameters

	<i>v</i>	The buffer for string.
<i>in, out</i>	<i>size</i>	Input: The number of bytes available in <i>v</i> Output: The number of bytes received (including the terminator).

Definition at line 189 of file [ipc\\_stream](#).

The documentation for this class was generated from the following file:

- [l4/cxx/ipc\\_stream](#)

## 15.141 L4::lpc::Varg Class Reference

Variably sized RPC argument.

```
#include <ipc_varg>
```

Collaboration diagram for L4::lpc::Varg:

L4::lpc::Varg
<ul style="list-style-type: none"> <li>+ type()</li> <li>+ length()</li> <li>+ tag()</li> <li>+ tag()</li> <li>+ data()</li> <li>+ data()</li> <li>+ Varg()</li> <li>+ Varg()</li> <li>+ value()</li> <li>+ is_of()</li> <li>and 8 more...</li> </ul>



## Public Types

- typedef [l4\\_umword\\_t](#) **Tag**

*The data type for the tag.*

## Public Member Functions

- [L4\\_varg\\_type](#) [type](#) () const
- unsigned [length](#) () const  
*Get the size of the RPC argument.*
- [Tag](#) [tag](#) () const
- void **tag** ([Tag](#) tag)  
*Set [Varg](#) tag (usually from message).*
- void **data** (char const \*d)  
*Set [Varg](#) to indirect data value (usually in UTCB).*
- char const \* [data](#) () const
- **Varg** ()=default  
*Make uninitialized [Varg](#).*
- **Varg** ([L4\\_varg\\_type](#) t, void const \*v, int len)  
*Make an indirect varg.*
- template<typename V>  
  [Va\\_type](#)< V >::Ret\_value [value](#) () const
- template<typename T>  
  bool [is\\_of](#) () const
- bool [is\\_nil](#) () const
- bool [is\\_of\\_int](#) () const
- template<typename T>  
  bool [get\\_value](#) (typename [Va\\_type](#)< T >::Value \*v) const  
*Get the value of the [Varg](#) as type T.*
- template<typename T>  
  void **set\_value** (void const \*d)  
*Set to indirect value of type T.*
- template<typename T>  
  void **set\_direct\_value** (T val, typename [L4::Types::Enable\\_if](#)< sizeof(T)<=sizeof(char const \*), bool >::type=true)  
*Set to directly stored value of type T.*
- template<typename T>  
  **Varg** (T const \*[data](#))  
*Make [Varg](#) from indirect value (pointer).*
- **Varg** (char const \*[data](#))  
*Make [Varg](#) from null-terminated string.*
- template<typename T>  
  **Varg** (T [data](#), typename [L4::Types::Enable\\_if](#)< sizeof(T)<=sizeof(char const \*), bool >::type=true)  
*Make [Varg](#) from direct value.*

### 15.141.1 Detailed Description

Variably sized RPC argument.

Definition at line 96 of file [ipc\\_varg](#).

## 15.141.2 Member Function Documentation

### 15.141.2.1 data()

```
char const * L4::Ipc::Varg::data () const [inline]
```

#### Returns

pointer to the data, also safe for direct data

Definition at line 123 of file [ipc\\_varg](#).

### 15.141.2.2 get\_value()

```
template<typename T>
bool L4::Ipc::Varg::get_value (
    typename Va_type< T >::Value * v) const [inline]
```

Get the value of the [Varg](#) as type T.

#### Template Parameters

<i>T</i>	The expected type of the <a href="#">Varg</a> .
----------	---

#### Parameters

<i>v</i>	Pointer to store the value
----------	----------------------------


#### Returns

true when the [Varg](#) is of type T, false if not

Definition at line 185 of file [ipc\\_varg](#).

References [is\\_of\(\)](#), and [value\(\)](#).

Here is the call graph for this function:



### 15.141.2.3 is\_nil()

```
bool L4::Ipc::Varg::is_nil () const [inline]
```

#### Returns


true if the [Varg](#) is of nil type.

Definition at line 172 of file [ipc\\_varg](#).

References [is\\_of\(\)](#).

Referenced by [L4::Ipc::Varg\\_list\\_ref::iterator::equals\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 15.141.2.4 is\_of()

```
template<typename T>  
bool L4::Ipc::Varg::is_of () const [inline]
```

**Returns**

true if the [Varg](#) is of type T

Definition at line 169 of file [ipc\\_varg](#).


References [type\(\)](#).

Referenced by [get\\_value\(\)](#), and [is\\_nil\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:

**15.141.2.5 is\_of\_int()**

```
bool L4::Ipc::Varg::is_of_int () const [inline]
```

**Returns**

true if the [Varg](#) is an integer type (signed or unsigned).

Definition at line 175 of file [ipc\\_varg](#).

References [type\(\)](#).

Here is the call graph for this function:



**15.141.2.6 length()**

```
unsigned L4::Ipc::Varg::length () const [inline]
```

Get the size of the RPC argument.

**Returns**

The size of the RPC argument

Definition at line 114 of file [ipc\\_varg](#).

**15.141.2.7 tag()**

```
Tag L4::Ipc::Varg::tag () const [inline]
```

**Returns**

the tag value (the Direct\_data bit masked)

Definition at line 116 of file [ipc\\_varg](#).

Referenced by [tag\(\)](#).

Here is the caller graph for this function:

**15.141.2.8 type()**

```
L4_varg_type L4::Ipc::Varg::type () const [inline]
```


**Returns**

the type field of the tag

Definition at line 109 of file [ipc\\_varg](#).

Referenced by [is\\_of\(\)](#), [is\\_of\\_int\(\)](#), [set\\_direct\\_value\(\)](#), and [Varg\(\)](#).

Here is the caller graph for this function:



**15.141.2.9 value()**

```
template<typename V>
Va_type< V >::Ret_value L4::Ipc::Varg::value () const [inline]
```

**Template Parameters**

<b>V</b>	The data type of the value to retrieve.
----------	---

**Precondition**

The [Varg](#) must be of type *V* (otherwise the result is unpredictable).


**Returns**

The value of the [Varg](#) as type *V*.

Definition at line [155](#) of file [ipc\\_varg](#).

Referenced by [get\\_value\(\)](#).

Here is the caller graph for this function:



The documentation for this class was generated from the following file:


- `l4/sys/cxx/ipc_varg`

**15.142 L4::Ipc::Varg\_list< MAX > Class Template Reference**


Self-contained list of variable-sized RPC parameters.

```
#include <ipc_varg>
```

Inheritance diagram for L4::lpc::Varg\_list< MAX >:



Collaboration diagram for L4::lpc::Varg\_list< MAX >:



### Public Member Functions

- **Varg\_list** ([Varg\\_list\\_ref](#) const &r)  
*Create a parameter list as a copy from a referencing list.*

### Public Member Functions inherited from [L4::lpc::Varg\\_list\\_ref](#)

- **Varg\_list\_ref** ()=default  
*Create an empty parameter list.*
- [Varg\\_list\\_ref](#) (void const \*start, void const \*end)  
*Create a parameter list over a given memory region.*
- [Varg](#) **pop\_front** ()  
*Get the next parameter in the list.*
- [Varg](#) **next** ()  
*Get the next parameter in the list.*
- [Iterator](#) **begin** () const  
*Returns an iterator to the first [Varg](#).*
- [Iterator](#) **end** () const  
*Returns the end of the list.*



### 15.142.1 Detailed Description

```
template<unsigned MAX>
class L4::lpc::Varg_list< MAX >
```

Self-contained list of variable-sized RPC parameters.

Works like [Varg\\_list\\_ref](#) but contains a full copy of the data. Use this as a parameter in server functions, if the handler function needs to use the UTCB (e.g. while sending further IPC).

Definition at line 411 of file [ipc\\_varg](#).

The documentation for this class was generated from the following file:


- [l4/sys/cxx/ipc\\_varg](#)

## 15.143 L4::lpc::Varg\_list\_ref Class Reference

List of variable-sized RPC parameters as received by the server.

```
#include <ipc_varg>
```

Inheritance diagram for L4::lpc::Varg\_list\_ref:



Collaboration diagram for L4::lpc::Varg\_list\_ref:

L4::lpc::Varg_list_ref
<ul style="list-style-type: none"> <li>+ Varg_list_ref()</li> <li>+ Varg_list_ref()</li> <li>+ pop_front()</li> <li>+ next()</li> <li>+ begin()</li> <li>+ end()</li> </ul>

## Data Structures

- class [Iterator](#)  
*Iterator for Valists.*

## Public Member Functions

- **Varg\_list\_ref** ()=default  
*Create an empty parameter list.*
- **Varg\_list\_ref** (void const \*start, void const \*end)  
*Create a parameter list over a given memory region.*
- **Varg pop\_front** ()  
*Get the next parameter in the list.*
- **Varg next** ()  
*Get the next parameter in the list.*
- **Iterator begin** () const  
*Returns an iterator to the first Varg.*
- **Iterator end** () const  
*Returns the end of the list.*

### 15.143.1 Detailed Description

List of variable-sized RPC parameters as received by the server.

The list can be traversed exactly once using [next\(\)](#).

This is a reference list, where the returned [Varg](#) point to data in the underlying storage, conventionally the UTCB. This type should only be used in server functions when the implementation can ensure that all content is read before the UTCB is reused (e.g. for IPC), otherwise use [Varg\\_list](#).

Definition at line 253 of file [ipc\\_varg](#).

## 15.143.2 Constructor & Destructor Documentation

### 15.143.2.1 Varg\_list\_ref()

```
L4::Ipc::Varg_list_ref::Varg_list_ref (
    void const * start,
    void const * end) [inline]
```

Create a parameter list over a given memory region.


#### Parameters

<i>start</i>	Pointer to start of the parameter list.
<i>end</i>	Pointer to end of the list (inclusive).

Definition at line [332](#) of file [ipc\\_varg](#).

References [end\(\)](#).

Here is the call graph for this function:



The documentation for this class was generated from the following file:


- [l4/sys/cxx/ipc\\_varg](#)

## 15.144 L4::lpc::Varg\_list\_ref::Iterator Class Reference

[Iterator](#) for Valists.

```
#include <ipc_varg>
```

Collaboration diagram for L4::lpc::Varg\_list\_ref::Iterator:



### Public Member Functions

- **Iterator** (Iter\_state const &s)  
*Create a new iterator.*
- **operator bool** () const  
*validity check for the iterator*
- **Iterator** & **operator++** ()  
*increment iterator to the next arg*
- **Varg** **operator\*** () const  
*dereference the iterator, get [Varg](#)*
- bool **equals** (**Iterator** const &o) const  
*check for equality*

### 15.144.1 Detailed Description

[Iterator](#) for Valists.

Definition at line 338 of file [ipc\\_varg](#).

The documentation for this class was generated from the following file:


- l4/sys/cxx/ipc\_varg

## 15.145 L4::lpc\_gate Class Reference


The C++ IPC gate interface, see [IPC-Gate API](#) for the C interface.

```
#include <ipc_gate>
```

Inheritance diagram for L4::lpc\_gate:



Collaboration diagram for L4::lpc\_gate:



### Public Member Functions

- `l4_msgtag_t get_infos (l4_umword_t *label)`  
Get information about the IPC-gate.

### Public Member Functions inherited from L4::Rcv\_endpoint

- `l4_msgtag_t bind_thread (lpc::Cap< Thread > t, l4_umword_t label)`

*Bind the IPC receive endpoint to a thread.*

- [l4\\_msgtag\\_t bind\\_snd\\_destination](#) ([Cap](#)< [Snd\\_destination](#) > [snd\\_dst](#), [l4\\_umword\\_t](#) label)

*Bind a send destination (a thread or thread group) to an IPC receive endpoint.*

## Public Member Functions inherited from [L4::Kobject](#)

- [l4\\_msgtag\\_t dec\\_refcnt](#) ([l4\\_mword\\_t](#) diff, [l4\\_utcb\\_t](#) \*utcb=[l4\\_utcb](#)())

*Decrement the in kernel reference counter for the object.*

## Additional Inherited Members

## Protected Types inherited from

[L4::Kobject\\_t](#)< [lpc\\_gate](#), [Rcv\\_endpoint](#), [L4\\_PROTO\\_KOBJECT](#), [Type\\_info::Demand\\_t](#)< 1 > >

- typedef [lpc\\_gate](#) **Class**

*The target interface type (inheriting from [Kobject\\_t](#)).*

- typedef [Typeid::Iface](#)< [PROTO](#), [lpc\\_gate](#) > **\_\_Iface**

*The interface description for the derived class.*

- typedef [Typeid::Merge\\_list](#)< [Typeid::Iface\\_list](#)< **\_\_Iface** >, typename [Rcv\\_endpoint::\\_\\_Iface\\_list](#) > **\_\_Iface\_list**

*The list of all RPC interfaces provided directly or through inheritance.*

## Protected Types inherited from

[L4::Kobject\\_t](#)< [Rcv\\_endpoint](#), [Kobject](#), [L4\\_PROTO\\_KOBJECT](#), [Type\\_info::Demand\\_t](#)< 1 > >

- typedef [Rcv\\_endpoint](#) **Class**

*The target interface type (inheriting from [Kobject\\_t](#)).*

- typedef [Typeid::Iface](#)< [PROTO](#), [Rcv\\_endpoint](#) > **\_\_Iface**

*The interface description for the derived class.*

- typedef [Typeid::Merge\\_list](#)< [Typeid::Iface\\_list](#)< **\_\_Iface** >, typename [Kobject::\\_\\_Iface\\_list](#) > **\_\_Iface\_list**

*The list of all RPC interfaces provided directly or through inheritance.*

## Protected Member Functions inherited from

[L4::Kobject\\_t](#)< [lpc\\_gate](#), [Rcv\\_endpoint](#), [L4\\_PROTO\\_KOBJECT](#), [Type\\_info::Demand\\_t](#)< 1 > >

- [L4::Cap](#)< [Class](#) > **c** () const noexcept

*Get the capability to ourselves.*

## Protected Member Functions inherited from

[L4::Kobject\\_t](#)< [Rcv\\_endpoint](#), [Kobject](#), [L4\\_PROTO\\_KOBJECT](#), [Type\\_info::Demand\\_t](#)< 1 > >

- [L4::Cap](#)< [Class](#) > **c** () const noexcept

*Get the capability to ourselves.*

## Protected Member Functions inherited from [L4::Kobject](#)

- [l4\\_cap\\_idx\\_t cap](#) () const noexcept  
*Return capability selector.*

## Static Protected Member Functions inherited from

[L4::Kobject\\_t< lpc\\_gate, Rcv\\_endpoint, L4\\_PROTO\\_KOBJECT, Type\\_info::Demand\\_t< 1 > >](#)

- static void [\\_\\_check\\_protocols\\_\\_](#) () noexcept  
*Helper to check for protocol conflicts.*

## Static Protected Member Functions inherited from

[L4::Kobject\\_t< Rcv\\_endpoint, Kobject, L4\\_PROTO\\_KOBJECT, Type\\_info::Demand\\_t< 1 > >](#)

- static void [\\_\\_check\\_protocols\\_\\_](#) () noexcept  
*Helper to check for protocol conflicts.*

### 15.145.1 Detailed Description

The C++ IPC gate interface, see [IPC-Gate API](#) for the C interface.

IPC gates are used to create secure communication channels between protection domains. An IPC gate can be created using the [L4::Factory](#) interface.

Depending on the permissions of the capability used, an IPC gate forwards IPC to the [L4::Thread](#) or [L4::Thread\\_group](#) the IPC gate is *bound* to (cf. [bind\\_thread\(\)](#) and [bind\\_snd\\_destination\(\)](#)). If the capability has the [L4\\_FPAGE\\_C\\_IPCGATE\\_SVR](#) permission, only IPC using a protocol different from the [L4\\_PROTO\\_KOBJECT](#) protocol is forwarded. Without the [L4\\_FPAGE\\_C\\_IPCGATE\\_SVR](#) permission, all IPC is forwarded. The latter is the usual case for a client in a client/server scenario. When not bound to a thread or thread group yet, the forwarded IPC blocks until the IPC gate is bound to a thread or thread group, or the IPC times out.

Forwarded IPC is always forwarded to the userland of the thread the IPC gate is bound to, either directly or indirectly using a thread group. That means, the [L4::Thread](#) interface of that thread is not accessible via an IPC gate. The [L4::lpc\\_gate](#) interface of an IPC gate is only accessible if the capability used has the [L4\\_FPAGE\\_C\\_IPCGATE\\_SVR](#) permission (cf. previous paragraph). Conversely that means, if the capability used lacks the [L4\\_FPAGE\\_C\\_IPCGATE\\_SVR](#) permission, [L4::lpc\\_gate](#) interface calls are forwarded to the thread or thread group the IPC gate is bound to instead of being processed by the IPC gate itself. In a client/server scenario, a client should only get IPC gate capabilities without [L4\\_FPAGE\\_C\\_IPCGATE\\_SVR](#) permission so the client cannot tamper with the IPC gate.

When binding an IPC gate to a thread or thread group, a user-defined, kernel protected, machine-word sized payload called the IPC gate's *label* is assigned to the IPC gate (note that the two least significant bits of the label must be zero; cf. [bind\\_thread\(\)](#) and [bind\\_snd\\_destination\(\)](#)). When a send-only IPC or call IPC is forwarded via an IPC gate, the label provided by the sender is ignored and replaced by the IPC gate's label where the two least significant bits are set to the [L4\\_CAP\\_FPAGE\\_S](#) and [L4\\_CAP\\_FPAGE\\_W](#) permissions of the capability used. The replaced label is only visible to the thread the IPC gate is bound to (or to the selected thread of the thread group the IPC gate is bound to) upon receive. However, the configured label of an IPC gate can also be queried via [get\\_infos\(\)](#) if the capability used has the [L4\\_FPAGE\\_C\\_IPCGATE\\_SVR](#) permission.

When deleting an IPC gate or when unbinding it from a thread or thread group, the label of IPC already in flight won't be changed. To ensure that no IPC from this IPC gate is received by a thread with an unexpected label, [L4::Thread::modify\\_senders\(\)](#) shall be used to change the labels of every pending IPC to that gate. This is also required if the label of an already bound IPC gate is changed. It is not necessary after binding the IPC gate to a thread or thread group for the first time.

When binding a currently bound IPC gate to a new thread or thread group, the same label should be used that was used with the old thread. Otherwise the old and the new thread need to synchronize to avoid IPC messages with unexpected labels.



**Include File**

```
#include <l4/sys/ipc_gate>
```

For the C interface refer to the C [IPC-Gate API](#).

**See also**

[Object Invocation](#)

Definition at line 85 of file [ipc\\_gate](#).

**15.145.2 Member Function Documentation****15.145.2.1 get\_infos()**

```
l4_msgtag_t L4::Ipc_gate::get_infos (
    l4_umword_t * label)
```

Get information about the IPC-gate.

**Parameters**

out	<i>label</i>	The label of the IPC gate is returned here.
-----	--------------	---

**Returns**

System call return tag.

**Precondition**

If the IPC gate capability used to invoke this operation does not possess the [L4\\_FPAGE\\_C\\_IPCGATE\\_SVR](#) right, the kernel will not perform the operation. Instead, the underlying IPC message will be forwarded to the thread or thread group the IPC gate is bound to, blocking the caller if the IPC gate is not bound yet.

References [get\\_infos\(\)](#).

Referenced by [get\\_infos\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



The documentation for this class was generated from the following file:


- [l4/sys/ipc\\_gate](#)

## 15.146 L4::lpc\_svr::Br\_manager\_no\_buffers Class Reference


Empty implementation of [Server\\_iface](#).

```
#include <ipc_server_loop>
```

Inheritance diagram for L4::lpc\_svr::Br\_manager\_no\_buffers:



Collaboration diagram for L4::lpc\_svr::Br\_manager\_no\_buffers:



### Public Member Functions

- int `alloc_buffer_demand` (`Demand` const &demand) override  
*Tells the server to allocate buffers for the given demand.*
- L4::Cap< void > `get_rcv_cap` (int) const override  
*Returns L4::Cap< void >::Invalid, we have no buffer management.*
- int `realloc_rcv_cap` (int) override  
*Returns -L4\_ENOMEM, we have no buffer management.*
- int `add_timeout` (`Timeout` \*, `l4_kernel_clock_t`) override  
*Returns -L4\_ENOSYS, we have no timeout queue.*
- int `remove_timeout` (`Timeout` \*) override  
*Returns -L4\_ENOSYS, we have no timeout queue.*

## Public Member Functions inherited from L4::lpc\_svr::Server\_iface

- **Server\_iface** ()  
*Make a server interface.*
- `template<typename T>`  
`L4::Cap< T > rcv_cap (int index) const`  
*Get given receive buffer as typed capability.*
- `L4::Cap< void > rcv_cap (int index) const`  
*Get receive cap with the given index as generic (void) type.*

## Protected Member Functions

- `unsigned first_free_br () const`  
*Returns 1 as first free buffer.*
- `void setup_wait (l4_utcb_t *utcb, L4::lpc_svr::Reply_mode)`  
*Setup wait function for the server loop (Server<>).*

## Additional Inherited Members

## Public Types inherited from L4::lpc\_svr::Server\_iface

- `typedef L4::Type_info::Demand Demand`  
*Data type expressing server-side demand for receive buffers.*

### 15.146.1 Detailed Description

Empty implementation of [Server\\_iface](#).

This implementation of [Server\\_iface](#) provides no buffer or timeout management at all it just returns errors for all calls that express other than empty demands. However, this may be useful for very simple servers that serve simple server objects only.

Definition at line 233 of file [ipc\\_server\\_loop](#).

### 15.146.2 Member Function Documentation

#### 15.146.2.1 alloc\_buffer\_demand()

```
int L4::lpc_svr::Br_manager_no_buffers::alloc_buffer_demand (
    Demand const & demand) [inline], [override], [virtual]
```

Tells the server to allocate buffers for the given demand.

#### Parameters

<i>demand</i>	The total server-side demand of receive buffers needed for a given interface, see <a href="#">Demand</a> .
---------------	--

This function is not called by user applications directly. Usually the server implementation or the registry implementation calls this function whenever a new object is registered at the server.

**Returns**


success (0) if demand is empty, -L4\_ENOMEM else.

Implements [L4::lpc\\_svr::Server\\_iface](#).

Definition at line 240 of file [ipc\\_server\\_loop](#).

References [L4\\_ENOMEM](#), [L4\\_EOK](#), and [L4::Type\\_info::Demand::no\\_demand\(\)](#).

Here is the call graph for this function:



The documentation for this class was generated from the following file:


- `l4/sys/cxx/ipc_server_loop`

## 15.147 L4::lpc\_svr::Compound\_reply Struct Reference


Mix in for LOOP\_HOOKS to always use compound reply and wait.

```
#include <ipc_server_loop>
```

Inheritance diagram for L4::lpc\_svr::Compound\_reply:



Collaboration diagram for L4::lpc\_svr::Compound\_reply:



### 15.147.1 Detailed Description

Mix in for LOOP\_HOOKS to always use compound reply and wait.

Definition at line 73 of file [ipc\\_server\\_loop](#).

The documentation for this struct was generated from the following file:

- l4/sys/cxx/ipc\_server\_loop


## 15.148 L4::lpc\_svr::Dbg\_dispatch< R, Exc, Printer > Struct Template Reference

Dispatch helper that, in addition to what [Exc\\_dispatch](#) does, prints exception messages.


```
#include <ipc_server_loop>
```



Inheritance diagram for L4::lpc\_svr::Dbg\_dispatch< R, Exc, Printer >:



Collaboration diagram for L4::lpc\_svr::Dbg\_dispatch< R, Exc, Printer >:



#### Public Member Functions

- **Dbg\_dispatch** (R [r](#), Printer p)

*Make an exception handling dispatcher.*

- `l4_msgtag_t operator()` (`l4_msgtag_t` tag, `l4_umword_t` obj, `l4_utcb_t *utcb`)

*Dispatch the call via `Direct_dispatch<R>()`, handle exceptions, and print the exception message.*

### 15.148.1 Detailed Description

```
template<typename R, typename Exc, typename Printer>
struct L4::lpc_svr::Dbg_dispatch< R, Exc, Printer >
```

Dispatch helper that, in addition to what `Exc_dispatch` does, prints exception messages.

#### Template Parameters

<i>R</i>	Data type of the registry used for dispatching to objects.
<i>Exc</i>	Data type of the exceptions that shall be caught. This data type must provide a member <code>err_no()</code> that returns the negative integer (int) error code for the exception. In addition, methods <code>str()</code> and <code>extra_str()</code> are required that return a c-string describing the error.
<i>Printer</i>	A type that provides a <code>printf()</code> member that is used (with the usual format string syntax) to print error messages.

This dispatcher wraps `Direct_dispatch<R>` with a try-catch (Exc).

Definition at line 184 of file `ipc_server_loop`.

The documentation for this struct was generated from the following file:


- `l4/sys/cxx/ipc_server_loop`

## 15.149 L4::lpc\_svr::Default\_loop\_hooks Struct Reference


Default LOOP\_HOOKS.

```
#include <ipc_server_loop>
```

Inheritance diagram for L4::lpc\_svr::Default\_loop\_hooks:



Collaboration diagram for L4::lpc\_svr::Default\_loop\_hooks:



### Additional Inherited Members

### Public Types inherited from L4::lpc\_svr::Server\_iface

- typedef L4::Type\_info::Demand Demand  
*Data type expressing server-side demand for receive buffers.*

### Public Member Functions inherited from L4::lpc\_svr::Br\_manager\_no\_buffers

- int alloc\_buffer\_demand (Demand const &demand) override  
*Tells the server to allocate buffers for the given demand.*
- L4::Cap< void > get\_rcv\_cap (int) const override  
*Returns L4::Cap< void > ::Invalid, we have no buffer management.*
- int realloc\_rcv\_cap (int) override  
*Returns -L4\_ENOMEM, we have no buffer management.*
- int add\_timeout (Timeout \*, l4\_kernel\_clock\_t) override  
*Returns -L4\_ENOSYS, we have no timeout queue.*
- int remove\_timeout (Timeout \*) override  
*Returns -L4\_ENOSYS, we have no timeout queue.*

## Public Member Functions inherited from L4::lpc\_svr::Server\_iface

- **Server\_iface** ()  
*Make a server interface.*
- `template<typename T>`  
`L4::Cap< T > rcv_cap` (int index) const  
*Get given receive buffer as typed capability.*
- `L4::Cap< void > rcv_cap` (int index) const  
*Get receive cap with the given index as generic (void) type.*

## Protected Member Functions inherited from L4::lpc\_svr::Br\_manager\_no\_buffers

- unsigned **first\_free\_br** () const  
*Returns 1 as first free buffer.*
- void **setup\_wait** (l4\_utcb\_t \*utcb, L4::lpc\_svr::Reply\_mode)  
*Setup wait function for the server loop (Server<>).*

### 15.149.1 Detailed Description

Default LOOP\_HOOKS.

Combination of [Ignore\\_errors](#), [Default\\_timeout](#), [Compound\\_reply](#), and [Br\\_manager\\_no\\_buffers](#).

Definition at line 285 of file [ipc\\_server\\_loop](#).

The documentation for this struct was generated from the following file:


- l4/sys/cxx/ipc\_server\_loop

## 15.150 L4::lpc\_svr::Default\_setup\_wait Struct Reference

Mix in for LOOP\_HOOKS for setup\_wait no op.

```
#include <ipc_server_loop>
```

Collaboration diagram for L4::lpc\_svr::Default\_setup\_wait:



### 15.150.1 Detailed Description

Mix in for LOOP\_HOOKS for setup\_wait no op.

Definition at line 84 of file [ipc\\_server\\_loop](#).

The documentation for this struct was generated from the following file:


- l4/sys/cxx/ipc\_server\_loop

## 15.151 L4::lpc\_svr::Default\_timeout Struct Reference


Mix in for LOOP\_HOOKS to use a 0 send and a infinite receive timeout.

```
#include <ipc_server_loop>
```

Inheritance diagram for L4::lpc\_svr::Default\_timeout:



Collaboration diagram for L4::lpc\_svr::Default\_timeout:



### 15.151.1 Detailed Description

Mix in for LOOP\_HOOKS to use a 0 send and a infinite receive timeout.

Definition at line 65 of file [ipc\\_server\\_loop](#).

The documentation for this struct was generated from the following file:


- l4/sys/cxx/ipc\_server\_loop

## 15.152 L4::lpc\_svr::Direct\_dispatch< R > Struct Template Reference

Direct dispatch helper, for forwarding dispatch calls to a registry *R*.


```
#include <ipc_server_loop>
```

Inheritance diagram for L4::lpc\_svr::Direct\_dispatch< R >:





Collaboration diagram for L4::lpc\_svr::Direct\_dispatch< R >:



### Public Member Functions

- **Direct\_dispatch** (R &r)  
*Make a direct dispatcher.*
- **l4\_msgtag\_t operator()** (l4\_msgtag\_t tag, l4\_umword\_t obj, l4\_utcb\_t \*utcb)  
*call operator forwarding to r.dispatch()*

### Data Fields

- R & r  
*stores a reference to the registry object*

## 15.152.1 Detailed Description

```
template<typename R>
struct L4::lpc_svr::Direct_dispatch< R >
```

Direct dispatch helper, for forwarding dispatch calls to a registry *R*.

### Template Parameters

<i>R</i>	Data type of the registry that is used for dispatching to different server objects, usually based on the protected IPC label.
----------	---

Definition at line 95 of file [ipc\\_server\\_loop](#).

The documentation for this struct was generated from the following file:


- l4/sys/cxx/ipc\_server\_loop

### 15.153 L4::lpc\_svr::Direct\_dispatch< R \* > Struct Template Reference


Direct dispatch helper, for forwarding dispatch calls via a pointer to a registry *R*.

```
#include <ipc_server_loop>
```

Inheritance diagram for L4::lpc\_svr::Direct\_dispatch< R \* >:



Collaboration diagram for L4::lpc\_svr::Direct\_dispatch< R \* >:



### Public Member Functions

- **Direct\_dispatch** (R \*r)  
*Make a direct dispatcher.*
- **l4\_msgtag\_t operator()** (l4\_msgtag\_t tag, l4\_umword\_t obj, l4\_utcb\_t \*utcb)  
*call operator forwarding to r->dispatch()*

### Data Fields

- R \* r  
*stores a pointer to the registry object*

## 15.153.1 Detailed Description

```
template<typename R>
struct L4::lpc_svr::Direct_dispatch< R * >
```

Direct dispatch helper, for forwarding dispatch calls via a pointer to a registry *R*.

### Template Parameters

<i>R</i>	Data type of the registry that is used for dispatching to different server objects, usually based on the protected IPC label.
----------	---

Definition at line 116 of file [ipc\\_server\\_loop](#).

The documentation for this struct was generated from the following file:


- l4/sys/cxx/ipc\_server\_loop

## 15.154 L4::lpc\_svr::Exc\_dispatch< R, Exc > Struct Template Reference


Dispatch helper wrapping try {} catch {} around the dispatch call.

```
#include <ipc_server_loop>
```

Inheritance diagram for L4::lpc\_svr::Exc\_dispatch< R, Exc >:



Collaboration diagram for L4::lpc\_svr::Exc\_dispatch< R, Exc >:



### Public Member Functions

- **Exc\_dispatch** (R r)  
*Make an exception handling dispatcher.*
- **l4\_msgtag\_t operator()** (l4\_msgtag\_t tag, l4\_umword\_t obj, l4\_utcb\_t \*utcb)  
*Dispatch the call via [Direct\\_dispatch<R>\(\)](#) and handle exceptions.*

### 15.154.1 Detailed Description

```
template<typename R, typename Exc>
struct L4::lpc_svr::Exc_dispatch< R, Exc >
```

Dispatch helper wrapping try {} catch {} around the dispatch call.

### Template Parameters

<i>R</i>	Data type of the registry used for dispatching to objects.
<i>Exc</i>	Data type of the exceptions that shall be caught. This data type must provide a member <code>err_no()</code> that returns the negative integer (int) error code for the exception.

This dispatcher wraps `Direct_dispatch<R>` with a try-catch (`Exc`).

Definition at line 140 of file [ipc\\_server\\_loop](#).

The documentation for this struct was generated from the following file:


- `l4/sys/cxx/ipc_server_loop`

## 15.155 L4::lpc\_svr::Ignore\_errors Struct Reference


Mix in for LOOP\_HOOKS to ignore IPC errors.

```
#include <ipc_server_loop>
```

Inheritance diagram for L4::lpc\_svr::Ignore\_errors:



Collaboration diagram for L4::lpc\_svr::Ignore\_errors:



### 15.155.1 Detailed Description

Mix in for LOOP\_HOOKS to ignore IPC errors.

Definition at line 57 of file [ipc\\_server\\_loop](#).

The documentation for this struct was generated from the following file:


- l4/sys/cxx/ipc\_server\_loop

## 15.156 L4::lpc\_svr::Server\_iface Class Reference

Interface for server-loop related functions.


```
#include <ipc_epiface>
```

Inheritance diagram for L4::lpc\_svr::Server\_iface:





Collaboration diagram for L4::lpc\_svr::Server\_iface:



## Public Types

- typedef [L4::Type\\_info::Demand](#) **Demand**  
*Data type expressing server-side demand for receive buffers.*

## Public Member Functions

- **Server\_iface** ()  
*Make a server interface.*
- virtual int [alloc\\_buffer\\_demand](#) ([Demand](#) const &demand)=0  
*Tells the server to allocate buffers for the given demand.*
- virtual [L4::Cap](#)< void > [get\\_rcv\\_cap](#) (int index) const =0  
*Get capability slot allocated to the given receive buffer.*
- virtual int [realloc\\_rcv\\_cap](#) (int index)=0  
*Allocate a new capability for the given receive buffer.*
- virtual int [add\\_timeout](#) ([Timeout](#) \*timeout, [l4\\_kernel\\_clock\\_t](#) time)=0  
*Add a timeout to the server internal timeout queue.*
- virtual int [remove\\_timeout](#) ([Timeout](#) \*timeout)=0  
*Remove the given timeout from the timer queue.*
- template<typename T>  
[L4::Cap](#)< T > [rcv\\_cap](#) (int index) const  
*Get given receive buffer as typed capability.*
- [L4::Cap](#)< void > [rcv\\_cap](#) (int index) const  
*Get receive cap with the given index as generic (void) type.*

### 15.156.1 Detailed Description

Interface for server-loop related functions.

This interface provides access to high-level server-loop related functions, such as management of receive buffers and timeouts.

Definition at line 36 of file [ipc\\_epiface](#).

### 15.156.2 Member Function Documentation

#### 15.156.2.1 add\_timeout()

```
virtual int L4::Ipc_svr::Server_iface::add_timeout (
    Timeout * timeout,
    l4_kernel_clock_t time) [pure virtual]
```

Add a timeout to the server internal timeout queue.

##### Parameters

<i>timeout</i>	The timeout object to register.
<i>time</i>	The time (absolute) at which the timeout shall expire.

##### Precondition

timeout must not be in any queue.

##### Returns

0 on success, 1 if timeout is already expired, < 0 on error.

Implemented in [L4::lpc\\_svr::Br\\_manager\\_no\\_buffers](#), [L4::lpc\\_svr::Timeout\\_queue\\_hooks< HOOKS, BR\\_MAN >](#), [L4::lpc\\_svr::Timeout\\_queue\\_hooks< Br\\_manager\\_timeout\\_hooks, Br\\_manager >](#), and [L4Re::Util::Br\\_manager](#).

#### 15.156.2.2 alloc\_buffer\_demand()

```
virtual int L4::Ipc_svr::Server_iface::alloc_buffer_demand (
    Demand const & demand) [pure virtual]
```

Tells the server to allocate buffers for the given demand.

##### Parameters

<i>demand</i>	The total server-side demand of receive buffers needed for a given interface, see <a href="#">Demand</a> .
---------------	--

This function is not called by user applications directly. Usually the server implementation or the registry implementation calls this function whenever a new object is registered at the server.

Implemented in [L4::lpc\\_svr::Br\\_manager\\_no\\_buffers](#), and [L4Re::Util::Br\\_manager](#).

**15.156.2.3 get\_rcv\_cap()**

```
virtual L4::Cap< void > L4::Ipc_svr::Server_iface::get_rcv_cap (
    int index) const [pure virtual]
```

Get capability slot allocated to the given receive buffer.

**Parameters**

<i>index</i>	The receive buffer index of the expected capability argument ( $0 \leq \text{index} < \text{caps}$ registered with <a href="#">alloc_buffer_demand()</a> ).
--------------	---

**Precondition**

$0 \leq \text{index} < \text{caps}$  registered with [alloc\\_buffer\\_demand\(\)](#)


**Returns**

Capability slot currently allocated to the given receive buffer.

Implemented in [L4::lpc\\_svr::Br\\_manager\\_no\\_buffers](#), and [L4Re::Util::Br\\_manager](#).

Referenced by [rcv\\_cap\(\)](#).

Here is the caller graph for this function:

**15.156.2.4 rcv\_cap()** [1/2]

```
L4::Cap< void > L4::Ipc_svr::Server_iface::rcv_cap (
    int index) const [inline]
```

Get receive cap with the given index as generic (void) type.

**Parameters**

<i>index</i>	The index of the cap receive buffer of the expected capability. ( $0 \leq \text{index} < \text{caps}$ registered with <a href="#">alloc_buffer_demand()</a> .)
--------------	--

**Returns**

Capability slot currently allocated to the given capability buffer.


**Note**

This is a convenience wrapper for [get\\_rcv\\_cap\(\)](#).

Definition at line 126 of file [ipc\\_epiface](#).

References [get\\_rcv\\_cap\(\)](#).

Here is the call graph for this function:

**15.156.2.5 rcv\_cap() [2/2]**

```

template<typename T>
L4::Cap< T > L4::lpc_svr::Server_iface::rcv_cap (
    int index) const [inline]
  
```

Get given receive buffer as typed capability.

**See also**

[get\\_rcv\\_cap\(\)](#)

**Parameters**

<i>index</i>	The receive buffer index of the expected capability argument. ( $0 \leq \text{index} < \text{caps}$ registered with <a href="#">alloc_buffer_demand()</a> .)
--------------	--

**Precondition**

$0 \leq \text{index} < \text{caps}$  registered with [alloc\\_buffer\\_demand\(\)](#)

**Returns**

Capability slot currently allocated to the given receive buffer.


**Note**

This is a convenience wrapper for [get\\_rcv\\_cap\(\)](#) to avoid [L4::cap\\_cast<>\(\)](#).

Definition at line 114 of file [ipc\\_epiface](#).

References [L4::cap\\_cast\(\)](#), and [get\\_rcv\\_cap\(\)](#).

Here is the call graph for this function:

**15.156.2.6 realloc\_rcv\_cap()**

```
virtual int L4::Ipc_svr::Server_iface::realloc_rcv_cap (
    int index) [pure virtual]
```

Allocate a new capability for the given receive buffer.

**Parameters**

<i>index</i>	The receive buffer index of the expected capability argument ( $0 \leq \text{index} < \text{caps}$ registered with <a href="#">alloc_buffer_demand()</a> ).
--------------	---

**Precondition**

$0 \leq \text{index} < \text{caps}$  registered with [alloc\\_buffer\\_demand\(\)](#)

**Returns**

0 on success, < 0 on error.

Implemented in [L4::lpc\\_svr::Br\\_manager\\_no\\_buffers](#), and [L4Re::Util::Br\\_manager](#).

### 15.156.2.7 remove\_timeout()

```
virtual int L4::Ipc_svr::Server_iface::remove_timeout (
    Timeout * timeout) [pure virtual]
```

Remove the given timeout from the timer queue.

#### Parameters

<i>timeout</i>	The timeout object to remove.
----------------	-------------------------------

#### Returns

0 on success, < 0 on error.

Implemented in [L4::lpc\\_svr::Br\\_manager\\_no\\_buffers](#), [L4::lpc\\_svr::Timeout\\_queue\\_hooks< HOOKS, BR\\_MAN >](#), [L4::lpc\\_svr::Timeout\\_queue\\_hooks< Br\\_manager\\_timeout\\_hooks, Br\\_manager >](#), and [L4Re::Util::Br\\_manager](#).

The documentation for this class was generated from the following file:


- [l4/sys/cxx/ipc\\_epiface](#)

## 15.157 L4::lpc\_svr::Timeout Class Reference


Callback interface for [Timeout\\_queue](#).

```
#include <ipc_timeout_queue>
```

Inheritance diagram for L4::lpc\_svr::Timeout:



Collaboration diagram for L4::lpc\_svr::Timeout:



## Public Member Functions

- **Timeout ()**  
*Make a timeout.*
- virtual **~Timeout ()=0**  
*Destroy a timeout.*
- virtual void **expired ()=0**  
*callback function to be called when timeout happened*
- **l4\_kernel\_clock\_t timeout () const**  
*return absolute timeout of this callback.*

## Public Member Functions inherited from cxx::H\_list\_item\_t< void >

- **H\_list\_item\_t ()**  
*Constructor.*
- **~H\_list\_item\_t () noexcept**  
*Destructor.*



### 15.157.1 Detailed Description

Callback interface for [Timeout\\_queue](#).

Definition at line 18 of file [ipc\\_timeout\\_queue](#).

### 15.157.2 Member Function Documentation

#### 15.157.2.1 expired()

```
virtual void L4::lpc_svr::Timeout::expired () [pure virtual]
```


callback function to be called when timeout happened

##### Note

The timeout object is already dequeued when this function is called, this means the timeout may be safely queued again within the [expired\(\)](#) function.

Referenced by [L4::lpc\\_svr::Timeout\\_queue::handle\\_expired\\_timeouts\(\)](#).

Here is the caller graph for this function:



#### 15.157.2.2 timeout()

```
l4_kernel_clock_t L4::lpc_svr::Timeout::timeout () const [inline]
```

return absolute timeout of this callback.

##### Returns

absolute timeout for this instance of the timeout.

##### Precondition

The timeout object must have been in a queue before, otherwise the timeout is not set.

Definition at line 42 of file [ipc\\_timeout\\_queue](#).

The documentation for this class was generated from the following file:


- `l4/cxx/ipc_timeout_queue`

## 15.158 L4::lpc\_svr::Timeout\_queue Class Reference

[Timeout](#) queue to be used in l4re server loop.

```
#include <ipc_timeout_queue>
```

Collaboration diagram for L4::lpc\_svr::Timeout\_queue:



### Public Types

- typedef [L4::lpc\\_svr::Timeout](#) **Timeout**  
Provide a local definition of [Timeout](#) for backward compatibility.

### Public Member Functions

- [l4\\_kernel\\_clock\\_t](#) [next\\_timeout](#) () const  
Get the time for the next timeout.
- bool [timeout\\_expired](#) ([l4\\_kernel\\_clock\\_t](#) now) const  
Determine if a timeout has happened.
- void [handle\\_expired\\_timeouts](#) ([l4\\_kernel\\_clock\\_t](#) now)  
run the callbacks of expired timeouts
- void [add](#) ([Timeout](#) \*timeout, [l4\\_kernel\\_clock\\_t](#) time)  
Add a timeout to the queue.
- void [remove](#) ([Timeout](#) \*timeout)  
Remove timeout from the queue.

### 15.158.1 Detailed Description

[Timeout](#) queue to be used in l4re server loop.

Definition at line 55 of file [ipc\\_timeout\\_queue](#).

## 15.158.2 Member Function Documentation

### 15.158.2.1 add()

```
void L4::Ipc_svr::Timeout_queue::add (
    Timeout * timeout,
    l4_kernel_clock_t time) [inline]
```

Add a timeout to the queue.

#### Parameters

<i>timeout</i>	timeout object to add
<i>time</i>	the time when the timeout expires

#### Precondition

*timeout* must not be in any queue already

Definition at line 111 of file [ipc\\_timeout\\_queue](#).

### 15.158.2.2 handle\_expired\_timeouts()

```
void L4::Ipc_svr::Timeout_queue::handle_expired_timeouts (
    l4_kernel_clock_t now) [inline]
```

run the callbacks of expired timeouts


#### Parameters

<i>now</i>	the current time.
------------	-------------------

Definition at line 91 of file [ipc\\_timeout\\_queue](#).

References [L4::lpc\\_svr::Timeout::expired\(\)](#).

Here is the call graph for this function:



### 15.158.2.3 next\_timeout()

```
l4_kernel_clock_t L4::Ipc_svr::Timeout_queue::next_timeout () const [inline]
```

Get the time for the next timeout.

#### Returns

the time for the next timeout or 0 if there is none

Definition at line 65 of file [ipc\\_timeout\\_queue](#).

Referenced by [timeout\\_expired\(\)](#).

Here is the caller graph for this function:



### 15.158.2.4 remove()

```
void L4::Ipc_svr::Timeout_queue::remove (
    Timeout * timeout) [inline]
```

Remove *timeout* from the queue.

#### Parameters

<i>timeout</i>	timeout to remove from timeout queue
----------------	--------------------------------------

#### Precondition

*timeout* must be in this queue

Definition at line 126 of file [ipc\\_timeout\\_queue](#).

### 15.158.2.5 timeout\_expired()

```
bool L4::lpc_svr::Timeout_queue::timeout_expired (
    l4_kernel_clock_t now) const [inline]
```

Determine if a timeout has happened.

#### Parameters

<i>now</i>	The current time.
------------	-------------------

#### Return values

<i>true</i>	There is at least one expired timeout in the queue. <i>false</i> No expired timeout in the queue.
-------------	---

Definition at line 81 of file [ipc\\_timeout\\_queue](#).

References [next\\_timeout\(\)](#).

Here is the call graph for this function:



The documentation for this class was generated from the following file:


- `l4/cxx/ipc_timeout_queue`

## 15.159 L4::lpc\_svr::Timeout\_queue\_hooks< HOOKS, BR\_MAN > Class Template Reference


Loop hooks mixin for integrating a timeout queue into the server loop.

```
#include <ipc_timeout_queue>
```

Inheritance diagram for L4::lpc\_svr::Timeout\_queue\_hooks< HOOKS, BR\_MAN >:



Collaboration diagram for L4::lpc\_svr::Timeout\_queue\_hooks< HOOKS, BR\_MAN >:



## Public Member Functions

- [l4\\_timeout\\_t timeout \(\)](#)  
*get the time for the next timeout*
- void **setup\_wait** ([l4\\_utcb\\_t](#) \*utcb, [L4::lpc\\_svr::Reply\\_mode](#) mode)  
*setup\_wait() for the server loop*
- [L4::lpc\\_svr::Reply\\_mode](#) **before\_reply** ([l4\\_msgtag\\_t](#), [l4\\_utcb\\_t](#) \*)  
*server loop hook*
- int **add\_timeout** ([Timeout](#) \*timeout, [l4\\_kernel\\_clock\\_t](#) time) override  
*Add a timeout to the queue for time time.*

- int [remove\\_timeout](#) ([Timeout](#) \*[timeout](#)) override  
*Remove timeout from the queue.*

## Public Member Functions inherited from [L4::lpc\\_svr::Server\\_iface](#)

- [Server\\_iface](#) ()  
*Make a server interface.*
- template<typename T>  
[L4::Cap](#)< T > [rcv\\_cap](#) (int index) const  
*Get given receive buffer as typed capability.*
- [L4::Cap](#)< void > [rcv\\_cap](#) (int index) const  
*Get receive cap with the given index as generic (void) type.*

## Public Member Functions inherited from [L4::lpc\\_svr::Br\\_manager\\_no\\_buffers](#)

- int [alloc\\_buffer\\_demand](#) ([Demand](#) const &demand) override  
*Tells the server to allocate buffers for the given demand.*
- [L4::Cap](#)< void > [get\\_rcv\\_cap](#) (int) const override  
*Returns [L4::Cap](#)<void> ::Invalid, we have no buffer management.*
- int [realloc\\_rcv\\_cap](#) (int) override  
*Returns -L4\_ENOMEM, we have no buffer management.*

## Data Fields

- [Timeout\\_queue](#) [queue](#)  
*Use this timeout queue.*

## Additional Inherited Members

## Public Types inherited from [L4::lpc\\_svr::Server\\_iface](#)

- typedef [L4::Type\\_info::Demand](#) [Demand](#)  
*Data type expressing server-side demand for receive buffers.*

## Protected Member Functions inherited from [L4::lpc\\_svr::Br\\_manager\\_no\\_buffers](#)

- unsigned [first\\_free\\_br](#) () const  
*Returns 1 as first free buffer.*
- void [setup\\_wait](#) ([l4\\_utcb\\_t](#) \*utcb, [L4::lpc\\_svr::Reply\\_mode](#))  
*Setup wait function for the server loop ([Server](#)<>).*



### 15.159.1 Detailed Description

```
template<typename HOOKS, typename BR_MAN = Br_manager_no_buffers>
class L4::lpc_svr::Timeout_queue_hooks< HOOKS, BR_MAN >
```

Loop hooks mixin for integrating a timeout queue into the server loop.

#### Template Parameters

<i>HOOKS</i>	has to inherit from <a href="#">Timeout_queue_hooks&lt;&gt;</a> and provide the functions <code>now()</code> that has to return the current time.
<i>BR_MAN</i>	This used as a base class for and provides the API for selecting the buffer register (BR) that is used to store the timeout value. This is usually <a href="#">L4Re::Util::Br_manager</a> or <a href="#">L4::lpc_svr::Br_manager_no_buffers</a> .

Definition at line 150 of file [ipc\\_timeout\\_queue](#).

### 15.159.2 Member Function Documentation

#### 15.159.2.1 add\_timeout()

```
template<typename HOOKS, typename BR_MAN = Br_manager_no_buffers>
int L4::lpc_svr::Timeout_queue_hooks< HOOKS, BR_MAN >::add_timeout (
    Timeout * timeout,
    l4_kernel_clock_t time) [inline], [override], [virtual]
```

Add a timeout to the queue for time *time*.

#### Parameters

<i>timeout</i>	The timeout object to add into the queue (must not be in any queue currently).
<i>time</i>	The time when the timeout shall expire.

#### Precondition

`timeout` must not be in any queue.

#### Note


The timeout is automatically dequeued before the [Timeout::expired\(\)](#) function is called

Implements [L4::lpc\\_svr::Server\\_iface](#).

Definition at line 202 of file [ipc\\_timeout\\_queue](#).

References [queue](#), and [timeout\(\)](#).

Here is the call graph for this function:



### 15.159.2.2 remove\_timeout()

```
template<typename HOOKS, typename BR_MAN = Br_manager_no_buffers>
int L4::Ipc_svr::Timeout_queue_hooks< HOOKS, BR_MAN >::remove_timeout (
    Timeout * timeout) [inline], [override], [virtual]
```

Remove timeout from the queue.

#### Parameters

<i>timeout</i>	The timeout object to be removed from the queue.
----------------	--

#### Note


This function may be safely called even if the timeout is not currently enqueued.  
in [Timeout::expired\(\)](#) the timeout is already dequeued!

Implements [L4::Ipc\\_svr::Server\\_iface](#).

Definition at line 215 of file [ipc\\_timeout\\_queue](#).

References [queue](#), and [timeout\(\)](#).

Here is the call graph for this function:



The documentation for this class was generated from the following file:


- [I4/cxx/ipc\\_timeout\\_queue](#)

## 15.160 L4::Irq Class Reference


C++ [Irq](#) interface, see [IRQs](#) for the C interface.

```
#include <irq>
```

Inheritance diagram for L4::lrq:



Collaboration diagram for L4::Irq:



## Public Member Functions

- `I4_msgtag_t bind_vcpu (L4::Cap< Thread > const &thread, I4_umword_t cfg, I4_utcb_t *utcb=I4_utcb()) noexcept`  
Bind a thread to this *Irq* for vCPU interrupt forwarding.
- `I4_msgtag_t detach (I4_utcb_t *utcb=I4_utcb()) noexcept`  
Detach from this interrupt.

- `l4_msgtag_t receive` (`l4_timeout_t` timeout=`L4_IPC_NEVER`, `l4_utcb_t` \*utcb=`l4_utcb`()) noexcept  
*Unmask and wait for this IRQ.*
- `l4_msgtag_t wait` (`l4_umword_t` \*label, `l4_timeout_t` timeout=`L4_IPC_NEVER`, `l4_utcb_t` \*utcb=`l4_utcb`()) noexcept  
*Unmask IRQ and (open) wait for any message.*
- `l4_msgtag_t unmask` (`l4_utcb_t` \*utcb=`l4_utcb`()) noexcept  
*Unmask this IRQ.*

## Public Member Functions inherited from `L4::Triggerable`

- `l4_msgtag_t trigger` (`l4_utcb_t` \*utcb=`l4_utcb`()) noexcept  
*Trigger the object.*

## Public Member Functions inherited from `L4::Irq_eoi`

- `l4_msgtag_t unmask` (unsigned irqnum, `l4_umword_t` \*label=0, `l4_timeout_t` to=`L4_IPC_NEVER`, `l4_utcb_t` \*utcb=`l4_utcb`()) noexcept  
*Unmask the given interrupt line.*

## Public Member Functions inherited from `L4::Rcv_endpoint`

- `l4_msgtag_t bind_thread` (`lpc::Cap`< `Thread` > t, `l4_umword_t` label)  
*Bind the IPC receive endpoint to a thread.*
- `l4_msgtag_t bind_snd_destination` (`Cap`< `Snd_destination` > snd\_dst, `l4_umword_t` label)  
*Bind a send destination (a thread or thread group) to an IPC receive endpoint.*

## Public Member Functions inherited from `L4::Kobject`

- `l4_msgtag_t dec_refcnt` (`l4_mword_t` diff, `l4_utcb_t` \*utcb=`l4_utcb`())  
*Decrement the in kernel reference counter for the object.*

## Additional Inherited Members

## Protected Types inherited from

### `L4::Kobject_2t`< `Irq`, `Triggerable`, `Rcv_endpoint`, `L4_PROTO_IRQ_SENDER` >

- typedef `Irq` Class  
*The target interface type (inheriting from `Kobject_t`).*
- typedef `Typeid::Iface`< `PROTO`, `Irq` > `__Iface`  
*The interface description for the derived class.*
- typedef `Typeid::Merge_list`< `Typeid::Iface_list`< `__Iface` >, `Typeid::Merge_list`< `typename Triggerable::__Iface_list`, `typename Rcv_endpoint::__Iface_list` > > `__Iface_list`  
*The list of all RPC interfaces provided directly or through inheritance.*

## Protected Types inherited from [L4::Kobject\\_t< Triggerable, Irq\\_eoi, L4\\_PROTO\\_IRQ >](#)

- typedef [Triggerable](#) **Class**  
*The target interface type (inheriting from [Kobject\\_t](#)).*
- typedef Typeid::Iface< PROTO, [Triggerable](#) > **\_\_Iface**  
*The interface description for the derived class.*
- typedef Typeid::Merge\_list< Typeid::Iface\_list< **\_\_Iface** >, typename Irq\_eoi::\_\_Iface\_list > **\_\_Iface\_list**  
*The list of all RPC interfaces provided directly or through inheritance.*

## Protected Types inherited from

### [L4::Kobject\\_t< Rcv\\_endpoint, Kobject, L4\\_PROTO\\_KOBJECT, Type\\_info::Demand\\_t< 1 > >](#)

- typedef [Rcv\\_endpoint](#) **Class**  
*The target interface type (inheriting from [Kobject\\_t](#)).*
- typedef Typeid::Iface< PROTO, [Rcv\\_endpoint](#) > **\_\_Iface**  
*The interface description for the derived class.*
- typedef Typeid::Merge\_list< Typeid::Iface\_list< **\_\_Iface** >, typename Kobject::\_\_Iface\_list > **\_\_Iface\_list**  
*The list of all RPC interfaces provided directly or through inheritance.*

## Protected Member Functions inherited from

### [L4::Kobject\\_2t< Irq, Triggerable, Rcv\\_endpoint, L4\\_PROTO\\_IRQ\\_SENDER >](#)

- [L4::Cap< Class > c](#) () const noexcept  
*Get the capability to ourselves.*

## Protected Member Functions inherited from

### [L4::Kobject\\_t< Triggerable, Irq\\_eoi, L4\\_PROTO\\_IRQ >](#)

- [L4::Cap< Class > c](#) () const noexcept  
*Get the capability to ourselves.*

## Protected Member Functions inherited from

### [L4::Kobject\\_t< Rcv\\_endpoint, Kobject, L4\\_PROTO\\_KOBJECT, Type\\_info::Demand\\_t< 1 > >](#)

- [L4::Cap< Class > c](#) () const noexcept  
*Get the capability to ourselves.*

## Protected Member Functions inherited from [L4::Kobject](#)

- [l4\\_cap\\_idx\\_t cap](#) () const noexcept  
*Return capability selector.*

## Static Protected Member Functions inherited from

### [L4::Kobject\\_2t< Irq, Triggerable, Rcv\\_endpoint, L4\\_PROTO\\_IRQ\\_SENDER >](#)

- static void [\\_\\_check\\_protocols\\_\\_](#) () noexcept  
*Helper to check for protocol conflicts.*

## Static Protected Member Functions inherited from [L4::Kobject\\_t< Triggerable, Irq\\_eoi, L4\\_PROTO\\_IRQ >](#)

- static void `__check_protocols__()` noexcept  
*Helper to check for protocol conflicts.*

## Static Protected Member Functions inherited from [L4::Kobject\\_t< Rcv\\_endpoint, Kobject, L4\\_PROTO\\_KOBJECT, Type\\_info::Demand\\_t< 1 > >](#)

- static void `__check_protocols__()` noexcept  
*Helper to check for protocol conflicts.*

### 15.160.1 Detailed Description

C++ [Irq](#) interface, see [IRQs](#) for the C interface.

#### Note

"IRQ" is short for "interrupt request". This is often used interchangeably for "interrupt"

The [Irq](#) class provides access to abstract interrupts provided by the microkernel. Interrupts may be

- hardware interrupts provided by the platform interrupt controller,
- virtual device interrupts provided by the microkernel's virtual devices (virtual serial or trace buffer) or
- virtual interrupts that can be triggered by user programs (IRQs) via the inherited method [L4::Triggerable::trigger\(\)](#).

For hardware and virtual device interrupts the [Irq](#) object must be bound to an interrupt source, see [L4::Icu](#). To receive interrupts, the [Irq](#) object must be bound to a thread, see [L4::Rcv\\_endpoint](#).

[Irq](#) objects can be created using a factory, see the [L4::Factory](#) API ([L4::Factory::create\(\)](#)).

#### Include File

```
#include <l4/sys/irq>
```

For the C interface refer to the [IRQs](#) API for an overview.

#### Examples

[examples/libs/l4re/c++/shared\\_ds/ds\\_clnt.cc](#).

Definition at line 120 of file [irq](#).

## 15.160.2 Member Function Documentation

### 15.160.2.1 bind\_vcpu()

```
l4_msgtag_t L4::Irq::bind_vcpu (
    L4::Cap< Thread > const & thread,
    l4_umword_t cfg,
    l4_utcb_t * utcb = l4_utcb()) [inline], [noexcept]
```

Bind a thread to this [lrq](#) for vCPU interrupt forwarding.

If the interrupt is triggered, the kernel will directly inject the interrupt into the guest. This requires that the thread is currently in extended vCPU user mode. Otherwise the interrupt will stay pending and gets injected on the next vCPU user mode transition. Optionally a doorbell [lrq](#) can be registered on the thread (see [Thread::register\\_doorbell\\_irq\(\)](#)) that is triggered in this case.

If a guest has acknowledged the interrupt but has not yet issued an EOI (i.e. the interrupt is in "active" state), it is not possible to bind the [lrq](#) to a new thread object. Either wait for the guest to issue the EOI or [detach\(\)](#) from the current thread. In this case the interrupt will stay active in the guest and it is the responsibility of the VMM to handle the eventual EOI of the guest.

#### Parameters

<i>thread</i>	<a href="#">Thread</a> object this <a href="#">lrq</a> shall be bound to.
<i>cfg</i>	Architecture specific interrupt configuration.
<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. See <a href="#">l4_utcb</a> .

#### Returns

Syscall return tag

#### Return values

<a href="#">-L4_EPERM</a>	Insufficient permissions; see precondition.
<a href="#">-L4_EBUSY</a>	Cannot bind to the new thread because interrupt is active on previous thread and guest has to issue end-of-interrupt first.
<a href="#">-L4_ENOSYS</a>	The kernel does not support direct interrupt forwarding.

#### Precondition


The invoked [lrq](#) capability and the capability `thread` both must have the permission [L4\\_CAP\\_FPAGE\\_S](#).

Definition at line [158](#) of file [irq](#).

References [L4::Cap\\_base::cap\(\)](#), [L4::Kobject::cap\(\)](#), and [l4\\_irq\\_bind\\_vcpu\\_u\(\)](#).



Here is the call graph for this function:



### 15.160.2.2 detach()

```
l4_msgtag_t L4::Irq::detach (
    l4_utcb_t * utcb = l4_utcb()) [inline], [noexcept]
```

Detach from this interrupt.

#### Parameters

<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. See <a href="#">l4_utcb</a> .
-------------	--

#### Returns

Syscall return tag

#### Return values

0	Successfully detached, there was no interrupt pending.
1	Successfully detached, there was an interrupt pending.
2	Successfully detached, an active vIRQ was abandoned.
-L4_EPERM	Insufficient permissions; see precondition.


#### Precondition

The invoked [irq](#) capability must have the permission [L4\\_CAP\\_FPAGE\\_S](#).

Definition at line 176 of file [irq](#).

References [L4::Kobject::cap\(\)](#), and [l4\\_irq\\_detach\\_u\(\)](#).

Here is the call graph for this function:



### 15.160.2.3 receive()

```

l4_msgtag_t L4::Irq::receive (
    l4_timeout_t timeout = L4_IPC_NEVER,
    l4_utcb_t * utcb = l4_utcb()) [inline], [noexcept]
  
```

Unmask and wait for this IRQ.

#### Parameters

<i>timeout</i>	Timeout.
<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. See <a href="#">l4_utcb</a> .

#### Returns

Syscall return tag


#### Note

If this is the function normally used for your IRQs consider using [L4::Semaphore](#) instead of [L4::Irq](#).

Definition at line 191 of file [irq](#).

References [L4::Kobject::cap\(\)](#), [L4\\_IPC\\_NEVER](#), and [I4\\_irq\\_receive\\_u\(\)](#).

Here is the call graph for this function:



## 15.160.2.4 unmask()

```
l4_msgtag_t L4::Irq::unmask (
    l4_utcb_t * utcb = l4_utcb()) [inline], [noexcept]
```

Unmask this IRQ.

## Parameters

<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. See <a href="#">l4_utcb</a> .
-------------	--

## Returns

Syscall return tag for a send-only operation, this means there is no return value except [L4\\_MSGTAG\\_ERROR](#) indicating success or failure of the send operation. Use [l4\\_ipc\\_error\(\)](#) to check for errors and **do not** use [l4\\_error\(\)](#).

[Irq::wait\(\)](#) and [Irq::receive\(\)](#) operations already include an [unmask\(\)](#), do not use an extra [unmask\(\)](#) in these cases.

Definition at line 221 of file [irq](#).

References [L4\\_IPC\\_NEVER](#), and [unmask\(\)](#).

Referenced by [unmask\(\)](#), and [wait\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 15.160.2.5 wait()

```
l4_msgtag_t L4::Irq::wait (
    l4_umword_t * label,
    l4_timeout_t timeout = L4_IPC_NEVER,
    l4_utcb_t * utcb = l4_utcb()) [inline], [noexcept]
```

Unmask IRQ and (open) wait for any message.

#### Parameters

<i>label</i>	The <i>protected label</i> shall be received here.
<i>timeout</i>	Timeout.
<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. See <a href="#">l4_utcb</a> .

#### Returns

Syscall return tag

Definition at line [204](#) of file [irq](#).

References [L4\\_IPC\\_NEVER](#), and [unmask\(\)](#).

Here is the call graph for this function:



The documentation for this class was generated from the following file:


- [l4/sys/irq](#)

## 15.161 L4::Irq\_eoi Class Reference


Interface for sending an unmask message to an object.

```
#include <irq>
```

Inheritance diagram for L4::Irq\_eoi:



Collaboration diagram for L4::Irq\_eoi:



## Public Member Functions

- [l4\\_msgtag\\_t unmask](#) (unsigned irqnum, [l4\\_umword\\_t](#) \*label=0, [l4\\_timeout\\_t](#) to=L4\_IPC\_NEVER, [l4\\_utcb\\_t](#) \*utcb=[l4\\_utcb\(\)](#)) noexcept  
*Unmask the given interrupt line.*

## 15.161.1 Detailed Description

Interface for sending an unmask message to an object.

The object is usually an ICU or an IRQ.

When the kernel receives an IRQ, it masks the interrupt line at the interrupt controller and immediately acknowledges the interrupt. This interface is used to let the kernel know that userspace has dealt with the IRQ. The kernel will unmask the interrupt line and further IRQs can then be delivered.

See also

[L4::lcu](#), [L4::irq](#)

Definition at line 37 of file [irq](#).

## 15.161.2 Member Function Documentation

### 15.161.2.1 unmask()

```
l4_msgtag_t L4::Irq_eoi::unmask (
    unsigned irqnum,
    l4_umword_t * label = 0,
    l4_timeout_t to = L4_IPC_NEVER,
    l4_utcb_t * utcb = l4_utcb()) [inline], [noexcept]
```

Unmask the given interrupt line.

When the object is an IRQ, the given interrupt line is ignored and instead the line which the IRQ is bound to (if any) is unmasked.

Its counterpart for explicitly masking an interrupt line is [L4::lcu::mask\(\)](#).

#### Parameters

	<i>irqnum</i>	The interrupt line that shall be unmasked. Ignored if the object is an IRQ.
out	<i>label</i>	If NULL, this is a send-only unmask. If not NULL, this operation enters an open wait and the <i>protected label</i> shall be received here.
	<i>to</i>	The timeout-pair (send and receive) that shall be used for this operation. The receive timeout is used with a non-NULL <i>label</i> only.
	<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. See <a href="#">l4_utcb</a> .

#### Returns

Syscall return tag. If *label* is NULL, this function performs an IPC send-only operation and there is no return value except [L4\\_MSGTAG\\_ERROR](#) indicating success or failure of the send operation. In this case use [l4\\_ipc\\_error\(\)](#) to check for errors and **do not** use [l4\\_error\(\)](#).

Definition at line 64 of file [irq](#).

References [L4::Kobject::cap\(\)](#), and [L4\\_IPC\\_NEVER](#).

Here is the call graph for this function:



The documentation for this class was generated from the following file:


- `l4/sys/irq`

## 15.162 L4::lrq\_handler\_object Struct Reference

[Server](#) object base class for handling IRQ messages.


```
#include <ipc_server>
```

Inheritance diagram for L4::lrq\_handler\_object:





Collaboration diagram for L4::lrq\_handler\_object:



#### Additional Inherited Members

#### Public Types inherited from [L4::Server\\_object\\_t< Kobject >](#)

- typedef [Kobject](#) **Interface**

*Data type of the IPC interface definition.*

## Public Types inherited from [L4::Epiface](#)

- typedef [lpc\\_svr::Server\\_iface](#) **Server\_iface**  
*Type for abstract server interface.*
- typedef [lpc\\_svr::Server\\_iface::Demand](#) **Demand**  
*Type for server-side receive buffer demand.*

## Public Member Functions inherited from [L4::Server\\_object\\_t< Kobject >](#)

- [L4::Server\\_object::Demand](#) [get\\_buffer\\_demand](#) () const override
- int [dispatch\\_meta\\_request](#) ([L4::lpc::lostream](#) &ios)  
*Implementation of the meta protocol based on IFACE.*

## Public Member Functions inherited from [L4::Server\\_object](#)

- virtual int [dispatch](#) (unsigned long rights, [lpc::lostream](#) &ios)=0  
*The abstract handler for client requests to the object.*
- [l4\\_msgtag\\_t](#) [dispatch](#) ([l4\\_msgtag\\_t](#) tag, unsigned rights, [l4\\_utcb\\_t](#) \*utcb) override  
*The abstract handler for client requests to the object.*

## Public Member Functions inherited from [L4::Epiface](#)

- **Epiface** ()  
*Make a server object.*
- virtual ~**Epiface** ()=0  
*Destroy the object.*
- Stored\_cap [obj\\_cap](#) () const  
*Get the capability to the kernel object belonging to this object.*
- [Server\\_iface](#) \* [server\\_iface](#) () const  
*Get pointer to server interface at which the object is currently registered.*
- int [set\\_server](#) ([Server\\_iface](#) \*srv, [Cap](#)< void > cap, bool managed=false)  
*Set server registration info for the object.*
- void [set\\_obj\\_cap](#) ([Cap](#)< void > const &cap)  
*Deprecated server registration function.*

## Static Public Member Functions inherited from [L4::Server\\_object\\_t< Kobject >](#)

- static int [proto\\_dispatch](#) (THIS \*self, [l4\\_umword\\_t](#) rights, [L4::lpc::lostream](#) &ios)  
*Implementation of protocol-based dispatch for this server object.*

### 15.162.1 Detailed Description

[Server](#) object base class for handling IRQ messages.

This server object base class implements the empty interface ([L4::Kobject](#)). The implementation of [Server\\_object::dispatch\(\)](#) must return [-L4\\_ENOREPLY](#), because IRQ messages do not handle replies.

#### Examples

[examples/libs/l4re/c++/shared\\_ds/ds\\_srv.cc](#).

Definition at line 161 of file [ipc\\_server](#).

The documentation for this struct was generated from the following file:


- [l4/cxx/ipc\\_server](#)

## 15.163 L4::lrqep\_t< Derived, BASE, bool > Struct Template Reference


[Epiface](#) implementation for interrupt handlers.

```
#include <ipc_epiface>
```

Inheritance diagram for L4::lrqep\_t< Derived, BASE, bool >:



Collaboration diagram for L4::lrqep\_t< Derived, BASE, bool >:



## Public Member Functions

- `l4_msgtag_t dispatch (l4_msgtag_t, unsigned, l4_utcb_t *)` final  
The abstract handler for client requests to the object.
- `Cap< L4::lrq > obj_cap ()` const  
Get the (typed) capability to this object.

**Public Member Functions inherited from L4::Epiface\_t0< void, Epiface >**

- [Type\\_info::Demand](#) **get\_buffer\_demand** () const  
*Get the server-side buffer demand based in IFACE.*
- [Cap](#)< void > **obj\_cap** () const  
*Get the (typed) capability to this object.*

**Public Member Functions inherited from L4::Epiface**

- **Epiface** ()  
*Make a server object.*
- virtual **~Epiface** ()=0  
*Destroy the object.*
- Stored\_cap [obj\\_cap](#) () const  
*Get the capability to the kernel object belonging to this object.*
- [Server\\_iface](#) \* **server\_iface** () const  
*Get pointer to server interface at which the object is currently registered.*
- int **set\_server** ([Server\\_iface](#) \*srv, [Cap](#)< void > cap, bool managed=false)  
*Set server registration info for the object.*
- void **set\_obj\_cap** ([Cap](#)< void > const &cap)  
*Deprecated server registration function.*

**Additional Inherited Members****Public Types inherited from L4::Epiface\_t0< void, Epiface >**

- typedef void **Interface**  
*Data type of the IPC interface definition.*

**Public Types inherited from L4::Epiface**

- typedef [lpc\\_svr::Server\\_iface](#) **Server\_iface**  
*Type for abstract server interface.*
- typedef [lpc\\_svr::Server\\_iface::Demand](#) **Demand**  
*Type for server-side receive buffer demand.*

**15.163.1 Detailed Description**

```
template<typename Derived, typename BASE = Epiface, bool = cxx::is_polymorphic<BASE>::value>
struct L4::Irqp_t< Derived, BASE, bool >
```

[Epiface](#) implementation for interrupt handlers.

**Template Parameters**

<i>Derived</i>	<a href="#">Irq</a> handler implementation class. The class must provide a single function <code>handle_irq()</code> .
----------------	--

<i>BASE</i>	Base <a href="#">Epiface</a> class.
-------------	-------------------------------------

Definition at line [282](#) of file [ipc\\_epiface](#).

## 15.163.2 Member Function Documentation

### 15.163.2.1 dispatch()

```
template<typename Derived, typename BASE = Epiface, bool = cxx::is_polymorphic<BASE>::value>
l4_msgtag_t L4::Irqep_t< Derived, BASE, bool >::dispatch (
    l4_msgtag_t tag,
    unsigned rights,
    l4_utcb_t * utcb) [inline], [final], [virtual]
```

The abstract handler for client requests to the object.

#### Parameters

<i>tag</i>	The message tag for this invocation.
<i>rights</i>	The rights bits in the invoked capability.
<i>utcb</i>	The UTCB used for the invocation.

#### Return values

<i>-L4_ENOREPLY</i>	No reply message is send.
<i>&lt;0</i>	Error, reply with error code.
<i>&gt;=0</i>	Success, reply with return value.


This function must be implemented by application specific server objects.

Implements [L4::Epiface](#).

Definition at line [284](#) of file [ipc\\_epiface](#).

References [L4\\_ENOREPLY](#), and [l4\\_msgtag\(\)](#).

Here is the call graph for this function:



### 15.163.2.2 obj\_cap()

```
template<typename Derived, typename BASE = Epiface, bool = cxx::is_polymorphic<BASE>::value>  
Cap< L4::Irq > L4::Irqep_t< Derived, BASE, bool >::obj_cap () const [inline]
```

Get the (typed) capability to this object.

#### Returns

[Irq](#) capability for the kernel object behind the server.

Definition at line 294 of file [ipc\\_epiface](#).

References [L4::cap\\_cast\(\)](#).

Here is the call graph for this function:



The documentation for this struct was generated from the following file:


- [l4/sys/cxx/ipc\\_epiface](#)

## 15.164 L4::Kip::Mem\_desc Class Reference

Memory descriptors stored in the kernel interface page.

```
#include <kip>
```

Collaboration diagram for L4::Kip::Mem\_desc:



## Public Types

- enum [Mem\\_type](#) {  
[Undefined](#) = 0x0 , [Conventional](#) = 0x1 , [Reserved](#) = 0x2 , [Dedicated](#) = 0x3 ,  
[Shared](#) = 0x4 , [Info](#) = 0xd , [Bootloader](#) = 0xe , [Arch](#) = 0xf }  
*Memory types.*
- enum [Info\\_sub\\_type](#) { [Info\\_acpi\\_rsd](#) = 0 , [Reserved\\_kernel](#) = 0 , [Reserved\\_heap](#) = 1 , [Reserved\\_mmio](#) = 2 }  
*Memory sub types for the [Mem\\_type::Info](#) type.*
- enum [Arch\\_sub\\_type\\_common](#) { [Arch\\_acpi\\_tables](#) = 3 , [Arch\\_acpi\\_nvs](#) = 4 }  
*Common sub types across all architectures for the [Mem\\_type::Arch](#) type.*

## Public Member Functions

- [Mem\\_desc](#) (unsigned long [start](#), unsigned long [end](#), [Mem\\_type](#) t, unsigned char st=0, bool virt=false, bool eager=false) noexcept  
*Initialize memory descriptor.*
- unsigned long [start](#) () const noexcept  
*Return start address of memory descriptor.*
- unsigned long [end](#) () const noexcept  
*Return end address of memory descriptor.*



- unsigned long [size](#) () const noexcept  
*Return size of region described by the memory descriptor.*
- [Mem\\_type](#) type () const noexcept  
*Return type of the memory descriptor.*
- unsigned char [sub\\_type](#) () const noexcept  
*Return sub-type of the memory descriptor.*
- unsigned [is\\_virtual](#) () const noexcept  
*Return whether the memory descriptor describes a virtual or physical region.*
- unsigned [eager\\_map](#) () const noexcept  
*Return whether the region shall be eligible for eager mapping in sigma0 or the root task.*
- void [set](#) (unsigned long [start](#), unsigned long [end](#), [Mem\\_type](#) t, unsigned char st=0, bool virt=false, bool eager=false) noexcept  
*Set values of a memory descriptor.*

### Static Public Member Functions

- static [Mem\\_desc](#) \* [first](#) ([l4\\_kernel\\_info\\_t](#) \*kip) noexcept  
*Get first memory descriptor.*
- static unsigned long [count](#) ([l4\\_kernel\\_info\\_t](#) const \*kip) noexcept  
*Return number of memory descriptors stored in the kernel info page.*
- static void [count](#) ([l4\\_kernel\\_info\\_t](#) \*kip, unsigned count) noexcept  
*Set number of memory descriptors.*
- static [cxx::static\\_vector](#)< [Mem\\_desc](#) const > [all](#) ([l4\\_kernel\\_info\\_t](#) const \*kip)  
*Return enumerable list of memory descriptors.*
- static [cxx::static\\_vector](#)< [Mem\\_desc](#) > [all](#) ([l4\\_kernel\\_info\\_t](#) \*kip)  
*Return enumerable list of memory descriptors.*

## 15.164.1 Detailed Description

Memory descriptors stored in the kernel interface page.

### Include File

```
#include <l4/sys/kip>
```

Definition at line 42 of file [kip](#).

## 15.164.2 Member Enumeration Documentation

### 15.164.2.1 Arch\_sub\_type\_common

```
enum L4::Kip::Mem_desc::Arch_sub_type_common
```

Common sub types across all architectures for the [Mem\\_type::Arch](#) type.

### Enumerator

---

Arch_acpi_tables	Firmware ACPI tables.
Arch_acpi_nvs	Firmware reserved address space.

Definition at line 76 of file [kip](#).

### 15.164.2.2 Info\_sub\_type

```
enum L4::Kip::Mem_desc::Info_sub_type
```

Memory sub types for the [Mem\\_type::Info](#) type.

#### Enumerator

Info_acpi_rsdp	Physical address of the ACPI root pointer.
Reserved_kernel	Kernel image.
Reserved_heap	Kernel heap.
Reserved_mmio	MMIO range reserved by kernel.

Definition at line 64 of file [kip](#).

### 15.164.2.3 Mem\_type

```
enum L4::Kip::Mem_desc::Mem_type
```

Memory types.

#### Enumerator

Undefined	Undefined memory.
Conventional	Conventional memory.
Reserved	Reserved region, do not use this memory.
Dedicated	Dedicated.
Shared	Shared.
Info	Info by boot loader.
Bootloader	Memory belongs to the boot loader.
Arch	Architecture specific memory.

Definition at line 48 of file [kip](#).

### 15.164.3 Constructor & Destructor Documentation

#### 15.164.3.1 Mem\_desc()

```
L4::Kip::Mem_desc::Mem_desc (
    unsigned long start,
    unsigned long end,
    Mem_type t,
    unsigned char st = 0,
    bool virt = false,
    bool eager = false) [inline], [noexcept]
```

Initialize memory descriptor.

#### Parameters


<i>start</i>	Start address
<i>end</i>	End address
<i>t</i>	Memory type
<i>st</i>	Memory subtype, defaults to 0
<i>virt</i>	True for virtual memory, false for physical memory, defaults to physical
<i>eager</i>	The region shall be eligible for eager mapping in sigma0 or the root task. This is just an optimization to prevent on-demand paging.

Definition at line 162 of file [kip](#).


References [end\(\)](#), and [start\(\)](#).

Referenced by [first\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



## 15.164.4 Member Function Documentation

### 15.164.4.1 `all()` [1/2]

```
cxx::static_vector< Mem_desc > L4::Kip::Mem_desc::all (
    l4_kernel_info_t * kip) [inline], [static]
```

Return enumerable list of memory descriptors.


#### Parameters

<i>kip</i>	Pointer to the kernel info page.
------------	----------------------------------

Definition at line 143 of file `kip`.

References `count()`, and `first()`.

Here is the call graph for this function:



### 15.164.4.2 `all()` [2/2]

```
cxx::static_vector< Mem_desc const > L4::Kip::Mem_desc::all (
    l4_kernel_info_t const * kip) [inline], [static]
```

Return enumerable list of memory descriptors.


#### Parameters

<i>kip</i>	Pointer to the kernel info page.
------------	----------------------------------

Definition at line 132 of file `kip`.

References `count()`, and `first()`.

Here is the call graph for this function:



### 15.164.4.3 count() [1/2]

```
void L4::Kip::Mem_desc::count (
    l4_kernel_info_t * kip,
    unsigned count) [inline], [static], [noexcept]
```

Set number of memory descriptors.


#### Parameters

<i>kip</i>	Pointer to the kernel info page
<i>count</i>	Number of memory descriptors

Definition at line 122 of file [kip](#).

References [count\(\)](#).

Here is the call graph for this function:



### 15.164.4.4 count() [2/2]

```
unsigned long L4::Kip::Mem_desc::count (
    l4_kernel_info_t const * kip) [inline], [static], [noexcept]
```

Return number of memory descriptors stored in the kernel info page.

#### Parameters

<i>kip</i>	Pointer to the kernel info page
------------	---------------------------------


**Returns**

Number of memory descriptors in the kernel info page.

Definition at line 111 of file [kip](#).

Referenced by [all\(\)](#), [all\(\)](#), and [count\(\)](#).

Here is the caller graph for this function:

**15.164.4.5 end()**

```
unsigned long L4::Kip::Mem_desc::end () const [inline], [noexcept]
```

Return end address of memory descriptor.


**Returns**

End address of memory descriptor

Definition at line 181 of file [kip](#).

Referenced by [Mem\\_desc\(\)](#), [set\(\)](#), and [size\(\)](#).

Here is the caller graph for this function:



#### 15.164.4.6 first()

```
Mem_desc * L4::Kip::Mem_desc::first (
    l4_kernel_info_t * kip) [inline], [static], [noexcept]
```

Get first memory descriptor.

##### Parameters

<i>kip</i>	Pointer to the kernel info page
------------	---------------------------------

##### Returns

First memory descriptor stored in the kernel info page

Definition at line 93 of file [kip](#).


References [Mem\\_desc\(\)](#).

Referenced by [all\(\)](#), and [all\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



**15.164.4.7 is\_virtual()**

```
unsigned L4::Kip::Mem_desc::is_virtual () const [inline], [noexcept]
```

Return whether the memory descriptor describes a virtual or physical region.

**Returns**

True for virtual region, false for physical region.

Definition at line 213 of file [kip](#).

**15.164.4.8 set()**

```
void L4::Kip::Mem_desc::set (
    unsigned long start,
    unsigned long end,
    Mem_type t,
    unsigned char st = 0,
    bool virt = false,
    bool eager = false) [inline], [noexcept]
```

Set values of a memory descriptor.


**Parameters**

<i>start</i>	Start address
<i>end</i>	End address
<i>t</i>	Memory type
<i>st</i>	Sub-type, defaults to 0
<i>virt</i>	Virtual or physical memory region, defaults to physical
<i>eager</i>	The region shall be eligible for eager mapping in sigma0 or the root task. This is just an optimization to prevent on-demand paging.

Definition at line 233 of file [kip](#).

References [end\(\)](#), and [start\(\)](#).

Here is the call graph for this function:





**15.164.4.9 size()**

```
unsigned long L4::Kip::Mem_desc::size () const [inline], [noexcept]
```

Return size of region described by the memory descriptor.


**Returns**

Size of the region described by the memory descriptor

Definition at line 188 of file [kip](#).

References [end\(\)](#), and [start\(\)](#).

Here is the call graph for this function:

**15.164.4.10 start()**

```
unsigned long L4::Kip::Mem_desc::start () const [inline], [noexcept]
```

Return start address of memory descriptor.


**Returns**

Start address of memory descriptor

Definition at line 174 of file [kip](#).

Referenced by [Mem\\_desc\(\)](#), [set\(\)](#), and [size\(\)](#).

Here is the caller graph for this function:





## Public Member Functions

- [l4\\_msgtag\\_t dec\\_refcnt](#) ([l4\\_mword\\_t diff](#), [l4\\_utcb\\_t \\*utcb=l4\\_utcb\(\)](#))  
*Decrement the in kernel reference counter for the object.*

## Protected Member Functions

- [l4\\_cap\\_idx\\_t cap](#) () const noexcept  
*Return capability selector.*

## 15.165.1 Detailed Description

Base class for all kinds of kernel objects and remote objects, referenced by capabilities.

### Include File

```
#include <l4/sys/capability>
```

This is the base class for all remote objects accessible using RPC. However, subclasses do not directly inherit from [L4::Kobject](#) but *must* use [L4::Kobject\\_t](#) ([L4::Kobject\\_0t](#), [L4::Kobject\\_2t](#), [L4::Kobject\\_3t](#), or [L4::Kobject\\_x](#)) for inheritance, otherwise these classes cannot be used as RPC interfaces.

### Attention

Objects derived from [Kobject](#) *must* never add any data to those objects. Kobjects can act only as proxy object for encapsulating object invocations.

Definition at line 36 of file [kobject](#).

## 15.165.2 Member Function Documentation

### 15.165.2.1 cap()

```
l4\_cap\_idx\_t L4::Kobject::cap () const [inline], [protected], [noexcept]
```

Return capability selector.

**Returns**

Capability selector.

This method is for derived classes to gain access to the actual capability selector.

Definition at line 69 of file [kobject](#).

Referenced by [L4::Thread\\_group::add\(\)](#), [L4::Debugger::add\\_image\\_info\(\)](#), [L4::Task::add\\_ku\\_mem\(\)](#), [L4Re::Mem\\_alloc::alloc\(\)](#), [L4vbus::Vbus::assign\\_dma\\_domain\(\)](#), [L4vbus::Vbus::assign\\_dma\\_domain\(\)](#), [L4::Icu::bind\(\)](#), [L4::Rcv\\_endpoint::bind\\_snd\\_destination\(\)](#), [L4::Irq::bind\\_vcpu\(\)](#), [L4::Task::cap\\_equal\(\)](#), [L4::Task::cap\\_valid\(\)](#), [L4::Thread::control\(\)](#), [L4::Factory::create\(\)](#), [L4::Factory::create\(\)](#), [L4::Factory::create\\_factory\(\)](#), [L4::Factory::create\\_gate\(\)](#), [L4::Factory::create\\_task\(\)](#), [L4::Factory::create\\_thread\\_group\(\)](#), [L4Re::Video::Goos::create\\_view\(\)](#), [dec\\_refcnt\(\)](#), [L4::Task::delete\\_obj\(\)](#), [L4::Irq::detach\(\)](#), [L4::Semaphore::down\(\)](#), [L4::Thread::ex\\_regs\(\)](#), [L4::Thread::ex\\_regs\(\)](#), [L4::Vcon::get\\_attr\(\)](#), [L4::Debugger::get\\_object\\_name\(\)](#), [L4::Debugger::global\\_id\(\)](#), [L4::Icu::info\(\)](#), [L4::Scheduler::is\\_online\(\)](#), [L4::Debugger::kobj\\_to\\_id\(\)](#), [L4::Task::map\(\)](#), [L4::Icu::mask\(\)](#), [L4::Thread::modify\\_senders\(\)](#), [L4::Debugger::query\\_log\\_name\(\)](#), [L4::Debugger::query\\_log\\_typeid\(\)](#), [L4::Debugger::query\\_object\\_name\(\)](#), [L4::Vcon::read\(\)](#), [L4::Vcon::read\\_with\\_flags\(\)](#), [L4::Irq::receive\(\)](#), [L4::Thread::register\\_del\\_irq\(\)](#), [L4::Thread::register\\_doorbell\\_irq\(\)](#), [L4::Task::release\\_cap\(\)](#), [L4vbus::Vbus::release\\_ioport\(\)](#), [L4::Thread\\_group::remove\(\)](#), [L4vbus::Vbus::request\\_ioport\(\)](#), [L4vbus::Vbus::root\(\)](#), [L4::Vcon::send\(\)](#), [L4::Vcon::set\\_attr\(\)](#), [L4::Icu::set\\_mode\(\)](#), [L4::Debugger::set\\_object\\_name\(\)](#), [L4::Thread::stats\\_time\(\)](#), [L4::Debugger::switch\\_log\(\)](#), [L4::Thread::switch\\_to\(\)](#), [L4::Triggerable::trigger\(\)](#), [L4::Icu::unbind\(\)](#), [L4::Task::unmap\(\)](#), [L4::Task::unmap\\_batch\(\)](#), [L4::Irq\\_eoi::unmask\(\)](#), [L4::Thread::vcpu\\_control\(\)](#), [L4::Thread::vcpu\\_control\\_ext\(\)](#), [L4::Thread::vcpu\\_resume\\_commit\(\)](#), [L4Re::Video::Goos::view\(\)](#), and [L4::Vcon::write\(\)](#).

[illegible]

```

14_msgtag_t L4::Kobject::dec_refcnt (
    14_mword_t diff,
    14_utcb_t * utcb = 14_utcb()) [inline]

```

Decrement the in kernel reference counter for the object.

#### Parameters

<i>diff</i>	The delta that shall be subtracted from the reference count.
<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. See <a href="#">l4_utcb</a> .

#### Returns

Syscall return tag

This function is intended for servers to be able to remove the servers own capability from the counted references. This leads to the semantics that the kernel will delete the object even if the capability of the server is valid. The server can detect the deletion by polling its capabilities or by using the IPC-gate deletion IRQs. And to cleanup if the clients dropped the last reference (capability) to the object.

This function only succeeds on a kernel object of type [L4::lpc\\_gate](#) which has the server right ([L4\\_FPAGE\\_C\\_IPCGATE\\_SVR](#)). For other kernel objects, -L4\_ENOSYS is returned.

Definition at line 100 of file [kobject](#).

References [cap\(\)](#).

Here is the call graph for this function:



The documentation for this class was generated from the following file:


- `l4/sys/kobject`

## 15.166 L4::Kobject\_2t< Derived, Base1, Base2, PROTO, S\_DEMAND > Class Template Reference


Helper class to create an [L4Re](#) interface class that is derived from two base classes (see [L4::Kobject\\_t](#)).

```
#include <l4/sys/capability>
```

Inheritance diagram for L4::Kobject\_2t< Derived, Base1, Base2, PROTO, S\_DEMAND >:



Collaboration diagram for L4::Kobject\_2t< Derived, Base1, Base2, PROTO, S\_DEMAND >:



## Protected Types

- typedef Derived [Class](#)  
The target interface type (inheriting from [Kobject\\_t](#)).
- typedef Typeid::Iface< PROTO, Derived > [\\_\\_Iface](#)  
The interface description for the derived class.
- typedef Typeid::Merge\_list< Typeid::Iface\_list< [\\_\\_Iface](#) >, Typeid::Merge\_list< typename Base1::\_\_Iface<\_\_Iface\_list, typename Base2::\_\_Iface\_list > > > [\\_\\_Iface\\_list](#)  
The list of all RPC interfaces provided directly or through inheritance.

## Protected Member Functions

- [L4::Cap< Class > c \(\)](#) const noexcept  
*Get the capability to ourselves.*

## Static Protected Member Functions

- static void [\\_\\_check\\_protocols\\_\\_ \(\)](#) noexcept  
*Helper to check for protocol conflicts.*

### 15.166.1 Detailed Description

```
template<typename Derived, typename Base1, typename Base2, l4\_proto\_t PROTO = PROTO_ANY, type-
name S_DEMAND = Type\_info::Demand\_t<>>
class L4::Kobject\_2t< Derived, Base1, Base2, PROTO, S_DEMAND >
```

Helper class to create an [L4Re](#) interface class that is derived from two base classes (see [L4::Kobject\\_t](#)).

#### Template Parameters

<i>Derived</i>	is the name of the new interface.
<i>Base1</i>	is the name of the interface's first base class.
<i>Base2</i>	is the name of the interface's second base class.
<i>PROTO</i>	may be set to the statically assigned protocol number used to communicate with this interface.
<i>S_DEMAND</i>	type defining the demand of server-side resources for this interface, usually a <a href="#">L4::Type_info::Demand_t</a> . This value must describe the server-side resources needed by the interface itself, the resource demand of the base interfaces (Base1 and Base2) are automatically included.

The typical usage pattern is shown in the following code snippet. The semantics of this example is an interface [My\\_iface](#) that is derived from [L4::Icu](#) and [L4Re::Dataspace](#).

```
class My\_iface : public L4::Kobject\_2t<My\_iface, L4::Icu, L4Re::Dataspace>
{
    ...
};
```

Definition at line [827](#) of file [\\_\\_typeinfo.h](#).

### 15.166.2 Member Typedef Documentation

#### 15.166.2.1 [\\_\\_Iface](#)

```
template<typename Derived, typename Base1, typename Base2, l4\_proto\_t PROTO = PROTO_ANY, typename
S_DEMAND = Type\_info::Demand\_t<>>
typedef Typeid::Iface<PROTO, Derived> L4::Kobject\_2t< Derived, Base1, Base2, PROTO, S_DEMAND
>::__Iface [protected]
```

The interface description for the derived class.

Definition at line [833](#) of file [\\_\\_typeinfo.h](#).



### 15.166.2.2 \_\_Iface\_list

```
template<typename Derived, typename Base1, typename Base2, l4_proto_t PROTO = PROTO_ANY, typename
S_DEMAND = Type_info::Demand_t<>>
typedef Typeid::Merge_list< Typeid::Iface_list<__Iface>, Typeid::Merge_list< typename Base1<
::__Iface_list, typename Base2::__Iface_list > > L4::Kobject_2t< Derived, Base1, Base2, PROTO,
S_DEMAND >::__Iface_list [protected]
```

The list of all RPC interfaces provided directly or through inheritance.

Definition at line 841 of file [\\_\\_typeinfo.h](#).

### 15.166.2.3 Class

```
template<typename Derived, typename Base1, typename Base2, l4_proto_t PROTO = PROTO_ANY, typename
S_DEMAND = Type_info::Demand_t<>>
typedef Derived L4::Kobject_2t< Derived, Base1, Base2, PROTO, S_DEMAND >::Class [protected]
```

The target interface type (inheriting from [Kobject\\_t](#)).

Definition at line 831 of file [\\_\\_typeinfo.h](#).

## 15.166.3 Member Function Documentation

### 15.166.3.1 \_\_check\_protocols\_\_()

```
template<typename Derived, typename Base1, typename Base2, l4_proto_t PROTO = PROTO_ANY, typename
S_DEMAND = Type_info::Demand_t<>>
void L4::Kobject_2t< Derived, Base1, Base2, PROTO, S_DEMAND >::__check_protocols__ () [inline],
[static], [protected], [noexcept]
```

Helper to check for protocol conflicts.

Definition at line 844 of file [\\_\\_typeinfo.h](#).

### 15.166.3.2 c()

```
template<typename Derived, typename Base1, typename Base2, l4_proto_t PROTO = PROTO_ANY, typename
S_DEMAND = Type_info::Demand_t<>>
L4::Cap< Class > L4::Kobject_2t< Derived, Base1, Base2, PROTO, S_DEMAND >::c () const [inline],
[protected], [noexcept]
```

Get the capability to ourselves.

Definition at line 863 of file [\\_\\_typeinfo.h](#).

The documentation for this class was generated from the following file:


- [l4/sys/\\_\\_typeinfo.h](#)

## 15.167 L4::Kobject\_3t< Derived, Base1, Base2, Base3, PROTO, S\_DEMAND > Struct Template Reference


Helper class to create an [L4Re](#) interface class that is derived from three base classes (see [L4::Kobject\\_t](#)).

```
#include <l4/sys/capability>
```

Inheritance diagram for L4::Kobject\_3t< Derived, Base1, Base2, Base3, PROTO, S\_DEMAND >:



Collaboration diagram for L4::Kobject\_3t< Derived, Base1, Base2, Base3, PROTO, S\_DEMAND >:



### Protected Types

- typedef Derived [Class](#)  
*The target interface type (inheriting from [Kobject\\_t](#)).*
- typedef Typeid::Iface< PROTO, Derived > [\\_\\_Iface](#)  
*The interface description for the derived class.*
- typedef Typeid::Merge\_list< Typeid::Iface\_list< [\\_\\_Iface](#) >, Typeid::Merge\_list< typename Base1::\_\_Iface\_list, Typeid::Merge\_list< typename Base2::\_\_Iface\_list, typename Base3::\_\_Iface\_list > > > [\\_\\_Iface\\_list](#)  
*The list of all RPC interfaces provided directly or through inheritance.*

### Protected Member Functions

- [L4::Cap](#)< [Class](#) > [c](#) () const noexcept  
*Get the capability to ourselves.*

### Static Protected Member Functions

- static void [\\_\\_check\\_protocols\\_\\_](#) () noexcept  
*Helper to check for protocol conflicts.*

## 15.167.1 Detailed Description

```
template<typename Derived, typename Base1, typename Base2, typename Base3, l4\_proto\_t PROTO =
PROTO_ANY, typename S_DEMAND = Type_info::Demand_t<>>
struct L4::Kobject_3t< Derived, Base1, Base2, Base3, PROTO, S_DEMAND >
```

Helper class to create an [L4Re](#) interface class that is derived from three base classes (see [L4 : Kobject\\_t](#)).

### Template Parameters

<i>Derived</i>	is the name of the new interface.
<i>Base1</i>	is the name of the interface's first base class.
<i>Base2</i>	is the name of the interface's second base class.
<i>Base3</i>	is the name of the interfaces third base class.
<i>PROTO</i>	may be set to the statically assigned protocol number used to communicate with this interface.
<i>S_DEMAND</i>	type defining the demand on server-side resources for this interface, usually a <a href="#">L4::Type_info::Demand_t</a> . This value must describe the server-side resources needed by the interface itself, the resource demand of the base interfaces (Base1 and Base2) are automatically included.

See also

[L4::Kobject\\_t](#), [L4::Kobject\\_2t](#), [L4::Kobject\\_0t](#), [L4::Kobject\\_x](#)

Definition at line 930 of file [\\_\\_typeinfo.h](#).

## 15.167.2 Member Typedef Documentation

### 15.167.2.1 \_\_Iface

```
template<typename Derived, typename Base1, typename Base2, typename Base3, l4\_proto\_t PROTO =
PROTO_ANY, typename S_DEMAND = Type_info::Demand_t<>>
typedef Typeid::Iface<PROTO, Derived> L4::Kobject\_3t< Derived, Base1, Base2, Base3, PROTO,
S_DEMAND >::__Iface [protected]
```

The interface description for the derived class.

Definition at line 936 of file [\\_\\_typeinfo.h](#).

### 15.167.2.2 \_\_Iface\_list

```
template<typename Derived, typename Base1, typename Base2, typename Base3, l4\_proto\_t PROTO =
PROTO_ANY, typename S_DEMAND = Type_info::Demand_t<>>
typedef Typeid::Merge_list< Typeid::Iface_list<\_\_Iface>, Typeid::Merge_list< typename Base1↵
::__Iface_list, Typeid::Merge_list< typename Base2::__Iface_list, typename Base3::__Iface↵
_list > > > L4::Kobject\_3t< Derived, Base1, Base2, Base3, PROTO, S_DEMAND >::__Iface_list
[protected]
```

The list of all RPC interfaces provided directly or through inheritance.

Definition at line 947 of file [\\_\\_typeinfo.h](#).

### 15.167.2.3 Class

```
template<typename Derived, typename Base1, typename Base2, typename Base3, l4\_proto\_t PROTO =
PROTO_ANY, typename S_DEMAND = Type_info::Demand_t<>>
typedef Derived L4::Kobject\_3t< Derived, Base1, Base2, Base3, PROTO, S_DEMAND >::Class [protected]
```

The target interface type (inheriting from [Kobject\\_t](#)).

Definition at line 934 of file [\\_\\_typeinfo.h](#).

### 15.167.3 Member Function Documentation

#### 15.167.3.1 \_\_check\_protocols\_\_()

```
template<typename Derived, typename Base1, typename Base2, typename Base3, l4_proto_t PROTO =
PROTO_ANY, typename S_DEMAND = Type_info::Demand_t<>>
void L4::Kobject_3t< Derived, Base1, Base2, Base3, PROTO, S_DEMAND >::__check_protocols__ ()
[inline], [static], [protected], [noexcept]
```

Helper to check for protocol conflicts.

Definition at line 950 of file [\\_\\_typeinfo.h](#).

#### 15.167.3.2 c()

```
template<typename Derived, typename Base1, typename Base2, typename Base3, l4_proto_t PROTO =
PROTO_ANY, typename S_DEMAND = Type_info::Demand_t<>>
L4::Cap< Class > L4::Kobject_3t< Derived, Base1, Base2, Base3, PROTO, S_DEMAND >::c () const
[inline], [protected], [noexcept]
```

Get the capability to ourselves.

Definition at line 978 of file [\\_\\_typeinfo.h](#).


The documentation for this struct was generated from the following file:

- [l4/sys/\\_\\_typeinfo.h](#)

## 15.168 L4::Kobject\_demand< T > Struct Template Reference

Get the combined server-side resource requirements for all type T...

Collaboration diagram for L4::Kobject\_demand< T >:



### 15.168.1 Detailed Description

```
template<typename ... T>
struct L4::Kobject_demand< T >
```

Get the combined server-side resource requirements for all type T...

#### Template Parameters

<i>T</i>	List of IPC interface types for which the combined server-side resource requirements shall be calculated.
----------	---

Definition at line 1031 of file [\\_\\_typeinfo.h](#).

The documentation for this struct was generated from the following file:


- [l4/sys/\\_\\_typeinfo.h](#)

### 15.169 L4::Kobject\_t< Derived, Base, PROTO, S\_DEMAND > Class Template Reference


Helper class to create an [L4Re](#) interface class that is derived from a single base class.

```
#include <l4/sys/capability>
```

Inheritance diagram for L4::Kobject\_t< Derived, Base, PROTO, S\_DEMAND >:



Collaboration diagram for L4::Kobject\_t< Derived, Base, PROTO, S\_DEMAND >:



## Protected Types

- typedef **Derived Class**  
The target interface type (inheriting from [Kobject\\_t](#)).
- typedef Typeid::Iface< PROTO, Derived > **\_\_Iface**  
The interface description for the derived class.
- typedef Typeid::Merge\_list< Typeid::Iface\_list< **\_\_Iface** >, typename Base::\_\_Iface\_list > **\_\_Iface\_list**  
The list of all RPC interfaces provided directly or through inheritance.

## Protected Member Functions

- [L4::Cap](#)< **Class** > **c** () const noexcept  
Get the capability to ourselves.

## Static Protected Member Functions

- static void **\_\_check\_protocols** () noexcept  
Helper to check for protocol conflicts.

## 15.169.1 Detailed Description

```
template<typename Derived, typename Base, l4\_proto\_t PROTO = PROTO_ANY, typename S_DEMAND =
Type_info::Demand_t<>>
class L4::Kobject_t< Derived, Base, PROTO, S_DEMAND >
```

Helper class to create an [L4Re](#) interface class that is derived from a single base class.

## Template Parameters

<i>Derived</i>	is the name of the new interface.
<i>Base</i>	is the name of the interfaces single base class.
<i>PROTO</i>	may be set to the statically assigned protocol number used to communicate with this interface.
<i>S_DEMAND</i>	type defining the demand on server-side resources for this interface, usually a <a href="#">L4::Type_info::Demand_t</a> . This value must describe the server-side resources needed by the interface itself, the resource demand of the base interface <i>Base</i> is automatically included.

The typical usage pattern is shown in the following code snippet. The semantics of this example is an interface *My\_iface* that is derived from [L4::Kobject](#).

```
class My_iface : public L4::Kobject_t<My_iface, L4::Kobject>
{
    ...
};
```

## Examples

[examples/clntsrv/src/shared.h](#).

Definition at line 749 of file [\\_\\_typeinfo.h](#).

The documentation for this class was generated from the following file:


- [l4/sys/\\_\\_typeinfo.h](#)

## 15.170 L4::Kobject\_typeid< T > Struct Template Reference


[Meta](#) object for handling access to type information of Kobjects.

```
#include <__typeinfo.h>
```

Inheritance diagram for L4::Kobject\_typeid< T >:



Collaboration diagram for L4::Kobject\_typeid< T >:





## Public Types

- typedef T::\_\_Kobject\_typeid::Demand [Demand](#)

*Data type expressing the static demand of receive buffers in a server.*

## Static Public Member Functions

- static [Type\\_info](#) const \* [id](#) () noexcept  
*Get a pointer to the [Kobject](#) type information of T.*
- static [Type\\_info::Demand](#) [demand](#) () noexcept  
*Get the receive-buffer demand for the server providing the interface T.*
- template<typename THIS, typename A1, typename A2>  
static int [proto\\_dispatch](#) (THIS \*self, [i4\\_proto\\_t](#) proto, A1 a1, A2 &a2)  
*Protocol based server-side dispatch function.*

## 15.170.1 Detailed Description

```
template<typename T>
struct L4::Kobject_typeid< T >
```

[Meta](#) object for handling access to type information of Kobjects.

### Template Parameters

<i>T</i>	The data type derived from <a href="#">Kobject</a> , usually using <a href="#">Kobject_t</a> .
----------	--

Definition at line 610 of file [\\_\\_typeinfo.h](#).

## 15.170.2 Member Typedef Documentation

### 15.170.2.1 Demand

```
template<typename T>
typedef T::__Kobject_typeid::Demand L4::Kobject\_typeid< T >::Demand
```

Data type expressing the static demand of receive buffers in a server.

This information is the combined demand of all base interfaces for T and the buffer demand of T itself. The buffer demand of T is usually specified as the S\_DEMAND argument of the [Kobject\\_t](#) or [Kobject\\_2t](#) inheritance helpers. S\_DEMAND is usually of type [L4::Type\\_info::Demand\\_t](#), or [L4::Type\\_info::Demand\\_union\\_t](#).

Definition at line 622 of file [\\_\\_typeinfo.h](#).

### 15.170.3 Member Function Documentation

#### 15.170.3.1 demand()

```
template<typename T>
Type_info::Demand L4::Kobject_typeid< T >::demand () [inline], [static], [noexcept]
```

Get the receive-buffer demand for the server providing the interface T.

##### Returns

A demand value describing the minimum receive buffers needed for handling server side requests for interface T.

Definition at line 639 of file [\\_\\_typeinfo.h](#).

#### 15.170.3.2 id()

```
template<typename T>
Type_info const * L4::Kobject_typeid< T >::id () [inline], [static], [noexcept]
```

Get a pointer to the [Kobject](#) type information of T.


##### Returns

a pointer to the [Kobject](#) typeinfo for of T.

Definition at line 630 of file [\\_\\_typeinfo.h](#).

Referenced by [L4::kobject\\_typeid\(\)](#).

Here is the caller graph for this function:



## 15.170.3.3 proto\_dispatch()

```

template<typename T>
template<typename THIS, typename A1, typename A2>
int L4::Kobject_typeid< T >::proto_dispatch (
    THIS * self,
    l4_proto_t proto,
    A1 a1,
    A2 & a2) [inline], [static]

```

Protocol based server-side dispatch function.

## Template Parameters

<i>THIS</i>	Data type of the server-side object implementing the interface T.
<i>A1</i>	Data type of second argument for p_dispatch()
<i>A2</i>	Data type of third argument for p_dispatch()

## Parameters


<i>self</i>	The pointer to the server object
<i>proto</i>	The protocol number used by the caller
<i>a1</i>	The second argument passed to self->p_dispatch()
<i>a2</i>	The third argument passed to self->p_dispatch()

This function forwards the call to the overloaded p\_dispatch() function of self. The data type of the first argument for p\_dispatch is determined by the given protocol number.

Definition at line 660 of file [\\_\\_typeinfo.h](#).

Referenced by [L4::Server\\_object\\_t< IFACE, BASE >::proto\\_dispatch\(\)](#).

Here is the caller graph for this function:



The documentation for this struct was generated from the following file:


- [l4/sys/\\_\\_typeinfo.h](#)

## 15.171 L4::Kobject\_typeid< void > Struct Reference


Minimalistic ID for void interface.

```
#include <__typeinfo.h>
```

Inheritance diagram for L4::Kobject\_typeid< void >:



Collaboration diagram for L4::Kobject\_typeid< void >:



### Static Public Member Functions

- static [Type\\_info](#) const \* [id](#) () noexcept  
*Get a pointer to the [Kobject](#) type information of T.*
- static [Type\\_info::Demand](#) [demand](#) () noexcept  
*Get the receive-buffer demand for the server providing the interface T.*
- static int [proto\\_dispatch](#) (THIS \*self, [l4\\_proto\\_t](#) proto, A1 a1, A2 &a2)  
*Protocol based server-side dispatch function.*

### 15.171.1 Detailed Description

Minimalistic ID for `void` interface.

Definition at line 667 of file [\\_\\_typeinfo.h](#).

### 15.171.2 Member Function Documentation

#### 15.171.2.1 demand()

```
Type_info::Demand L4::Kobject_typeid< void >::demand () [inline], [static], [noexcept]
```

Get the receive-buffer demand for the server providing the interface T.

**Returns**

A demand value describing the minimum receive buffers needed for handling server side requests for interface T.

Definition at line 639 of file [\\_\\_typeinfo.h](#).

**15.171.2.2 id()**

```
Type_info const * L4::Kobject_typeid< void >::id () [inline], [static], [noexcept]
```

Get a pointer to the [Kobject](#) type information of T.

**Returns**

a pointer to the [Kobject](#) typeinfo for of T.

Definition at line 630 of file [\\_\\_typeinfo.h](#).

**15.171.2.3 proto\_dispatch()**

```
int L4::Kobject_typeid< void >::proto_dispatch (
    THIS * self,
    l4_proto_t proto,
    A1 a1,
    A2 & a2) [inline], [static]
```

Protocol based server-side dispatch function.

**Template Parameters**

<i>THIS</i>	Data type of the server-side object implementing the interface T.
<i>A1</i>	Data type of second argument for p_dispatch()
<i>A2</i>	Data type of third argument for p_dispatch()

**Parameters**

<i>self</i>	The pointer to the server object
<i>proto</i>	The protocol number used by the caller
<i>a1</i>	The second argument passed to self->p_dispatch()
<i>a2</i>	The third argument passed to self->p_dispatch()

This function forwards the call to the overloaded p\_dispatch() function of self. The data type of the first argument for p\_dispatch is determined by the given protocol number.

Definition at line 660 of file [\\_\\_typeinfo.h](#).


The documentation for this struct was generated from the following file:

- [l4/sys/\\_\\_typeinfo.h](#)


## 15.172 L4::Kobject\_x< Derived, ARGS > Struct Template Reference

Generic [Kobject](#) inheritance template.

Inheritance diagram for L4::Kobject\_x< Derived, ARGS >:



Collaboration diagram for L4::Kobject\_x< Derived, ARGS >:



### 15.172.1 Detailed Description

```
template<typename Derived, typename ... ARGS>
struct L4::Kobject_x< Derived, ARGS >
```

Generic [Kobject](#) inheritance template.

#### Template Parameters

<i>Derived</i>	The class name that derives from <a href="#">Kobject_x</a> .
<i>ARGS</i>	An optional protocol number via <a href="#">L4::Proto_t</a> , followed by an optional server-side requirement passed as <a href="#">L4::Type_info::Demand_t</a> , followed by the list of base classes.

Definition at line [1197](#) of file [\\_\\_typeinfo.h](#).

The documentation for this struct was generated from the following file:


- [l4/sys/\\_\\_typeinfo.h](#)

## 15.173 L4::Lock\_guard Class Reference

Basic lock guard implementation that prevents forgotten unlocks on exit paths from a method or a block of code.

```
#include <lock_guard.h>
```

Collaboration diagram for L4::Lock\_guard:





## Public Member Functions

- [Lock\\_guard](#) (pthread\_mutex\_t &lock)  
*Construct the lock guard and lock the associated mutex.*
- [Lock\\_guard](#) (Lock\_guard &&guard)  
*Move constructor from other lock guard.*
- Lock\_guard & [operator=](#) (Lock\_guard &&guard)  
*Move assignment from other lock guard.*
- int [status](#) () const  
*Return last lock/unlock operation error status.*
- [~Lock\\_guard](#) ()  
*Lock guard destructor.*

### 15.173.1 Detailed Description

Basic lock guard implementation that prevents forgotten unlocks on exit paths from a method or a block of code.

Targeting pthread\_mutex\_t.

An instance of lock guard cannot be copied, but it can be moved.

The typical usage pattern of the lock guard is:

```
pthread_mutex_t mtx = PTHREAD_MUTEX_INITIALIZER;

{
    auto guard = L4Re::Lock_guard(mtx);

    // Correctness check.
    assert(guard.status() == 0);

    // Critical section protected by mtx.

    // The mtx is automatically unlocked when guard goes out of scope.
}
```

Definition at line 44 of file [lock\\_guard.h](#).

### 15.173.2 Constructor & Destructor Documentation

#### 15.173.2.1 Lock\_guard() [1/2]

```
L4::Lock_guard::Lock_guard (
    pthread_mutex_t & lock) [inline], [explicit]
```

Construct the lock guard and lock the associated mutex.

The error condition of the locking operation can be checked by the [status\(\)](#) method.

#### Parameters

<i>lock</i>	Associated mutex to be locked.
-------------	--------------------------------

Definition at line 59 of file [lock\\_guard.h](#).

### 15.173.2.2 Lock\_guard() [2/2]

```
L4::Lock_guard::Lock_guard (
    Lock_guard && guard) [inline]
```

Move constructor from other lock guard.

The mutex associated with the other lock guard is kept locked.

#### Parameters

<i>guard</i>	Lock guard to be moved.
--------------	-------------------------

Definition at line 71 of file [lock\\_guard.h](#).

### 15.173.2.3 ~Lock\_guard()

```
L4::Lock_guard::~~Lock_guard () [inline]
```

Lock guard destructor.

The associated mutex (if any) is unlocked.

There is no mechanism for indicating any error conditions. However, if the mutex has been previously locked successfully by this class and if the implementation of the mutex behaves according to the POSIX specification, the construction of this class guarantees that the unlock operation does not fail.

Definition at line 126 of file [lock\\_guard.h](#).

## 15.173.3 Member Function Documentation

### 15.173.3.1 operator=()

```
Lock_guard & L4::Lock_guard::operator= (
    Lock_guard && guard) [inline]
```

Move assignment from other lock guard.

The mutex currently associated with this lock guard is unlocked. The mutex associated with the other lock guard is kept locked.

There is no mechanism for indicating any error conditions of the unlocking operation. However, if the mutex has been previously locked successfully by this class and if the implementation of the mutex behaves according to the POSIX specification, the construction of this class guarantees that the unlock operation does not fail.

#### Parameters

<i>guard</i>	Lock guard to be moved.
--------------	-------------------------

Definition at line 90 of file [lock\\_guard.h](#).

### 15.173.3.2 status()

```
int L4::Lock_guard::status () const [inline]
```

Return last lock/unlock operation error status.

#### Returns

Zero indicating no errors, any other value indicating an error.

Definition at line 110 of file [lock\\_guard.h](#).

The documentation for this class was generated from the following file:


- [l4/cxx/lock\\_guard.h](#)

## 15.174 L4::Meta Class Reference


[Meta](#) interface that shall be implemented by each [L4Re](#) object and gives access to the dynamic type information for [L4Re](#) objects.

```
#include <meta>
```

Inheritance diagram for L4::Meta:



Collaboration diagram for L4::Meta:



## Public Member Functions

- [l4\\_msgtag\\_t num\\_interfaces \(\)](#)  
Get the number of interfaces implemented by this object.
- [l4\\_msgtag\\_t interface \(l4\\_umword\\_t idx, long \\*proto, L4::lpc::String< char > \\*name\)](#)  
Get the protocol number that must be used for the interface with the number *idx*.
- [l4\\_msgtag\\_t supports \(l4\\_mword\\_t protocol\)](#)  
Figure out if the object supports the given protocol (number).

## Public Member Functions inherited from [L4::Kobject](#)

- [l4\\_msgtag\\_t dec\\_refcnt \(l4\\_mword\\_t diff, l4\\_utcb\\_t \\*utcb=l4\\_utcb\(\)\)](#)  
Decrement the in kernel reference counter for the object.

## Additional Inherited Members

### Protected Types inherited from [L4::Kobject\\_t< Meta, Kobject, L4\\_PROTO\\_META >](#)

- typedef [Meta](#) **Class**  
*The target interface type (inheriting from [Kobject\\_t](#)).*
- typedef Typeid::Iface< PROTO, [Meta](#) > **\_\_iface**  
*The interface description for the derived class.*
- typedef Typeid::Merge\_list< Typeid::Iface\_list< **\_\_iface** >, typename Kobject::\_\_iface\_list > **\_\_iface\_list**  
*The list of all RPC interfaces provided directly or through inheritance.*

### Protected Member Functions inherited from [L4::Kobject\\_t< Meta, Kobject, L4\\_PROTO\\_META >](#)

- [L4::Cap< Class > c](#) () const noexcept  
*Get the capability to ourselves.*

### Protected Member Functions inherited from [L4::Kobject](#)

- [l4\\_cap\\_idx\\_t](#) [cap](#) () const noexcept  
*Return capability selector.*

### Static Protected Member Functions inherited from [L4::Kobject\\_t< Meta, Kobject, L4\\_PROTO\\_META >](#)

- static void [\\_\\_check\\_protocols\\_\\_](#) () noexcept  
*Helper to check for protocol conflicts.*

## 15.174.1 Detailed Description

[Meta](#) interface that shall be implemented by each [L4Re](#) object and gives access to the dynamic type information for [L4Re](#) objects.

Definition at line 26 of file [meta](#).

## 15.174.2 Member Function Documentation

### 15.174.2.1 interface()

```
l4_msgtag_t L4::Meta::interface (
    l4_umword_t idx,
    long * proto,
    L4::Ipc::String< char > * name)
```

Get the protocol number that must be used for the interface with the number `idx`.

#### Parameters

	<i>idx</i>	The index of the interface to get the protocol number for. <code>idx</code> must be $\geq 0$ and $<$ the return value of <code>num_interfaces()</code> .
out	<i>proto</i>	The protocol number for interface <code>idx</code> .
out	<i>name</i>	The protocol name for interface <code>idx</code> .

#### Return values

<code>l4_msgtag_t::label() == 0</code>	Successful; see <code>`proto`</code> and <code>`name`</code> .
<code>l4_msgtag_t::label() &lt; 0</code>	Error code.

Referenced by `num_interfaces()`.

Here is the caller graph for this function:



### 15.174.2.2 num\_interfaces()

```
l4_msgtag_t L4::Meta::num_interfaces ()
```

Get the number of interfaces implemented by this object.

#### Return values

<code>l4_msgtag_t::label() &gt;= 0</code>	The number of supported interfaces.
---	-------------------------------------

<code>l4_msgtag_t::label() &lt; 0</code>	Error code of the occurred error.
--	-----------------------------------


References [interface\(\)](#), and [num\\_interfaces\(\)](#).

Referenced by [num\\_interfaces\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 15.174.2.3 supports()

```
l4_msgtag_t L4::Meta::supports (
    l4_mword_t protocol)
```

Figure out if the object supports the given protocol (number).

#### Parameters

<i>protocol</i>	The protocol number to check for.
-----------------	-----------------------------------

#### Return values

<code>l4_msgtag_t::label() == 1</code>	protocol is supported.
<code>l4_msgtag_t::label() == 0</code>	protocol is not supported.



This method is intended to be used for statically assigned protocol numbers.

References [supports\(\)](#).

Referenced by [supports\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



The documentation for this class was generated from the following file:


- `l4/sys/meta`

## 15.175 L4::Out\_of\_memory Class Reference


[Exception](#) signalling insufficient memory.

```
#include <l4/cxx/exceptions>
```

Inheritance diagram for L4::Out\_of\_memory:



Collaboration diagram for L4::Out\_of\_memory:



### Public Member Functions

- **Out\_of\_memory** (char const \*extra="") noexcept  
*Create an out-of-memory exception.*
- **~Out\_of\_memory** () noexcept  
*Destruction.*

### Public Member Functions inherited from [L4::Runtime\\_error](#)

- [Runtime\\_error](#) (long [err\\_no](#), char const \*extra=0) noexcept  
*Create a new [Runtime\\_error](#).*
- char const \* [str](#) () const noexcept override  
*Return a human readable string for the exception.*
- char const \* [extra\\_str](#) () const  
*Get the description text for this runtime error.*
- long [err\\_no](#) () const noexcept  
*Get the error value for this runtime error.*

### Public Member Functions inherited from [L4::Base\\_exception](#)

- virtual ~[Base\\_exception](#) () noexcept  
*Destruction.*

### Public Member Functions inherited from [L4::Exception\\_tracer](#)

- void const \*const \* [pc\\_array](#) () const noexcept  
*Get the array containing the call trace.*
- int [frame\\_count](#) () const noexcept  
*Get the number of entries that are valid in the call trace.*

### Additional Inherited Members

### Protected Member Functions inherited from [L4::Base\\_exception](#)

- [Base\\_exception](#) () noexcept  
*Create a base exception.*

### Protected Member Functions inherited from [L4::Exception\\_tracer](#)

- [Exception\\_tracer](#) () noexcept  
*Create a back trace.*

## 15.175.1 Detailed Description

[Exception](#) signalling insufficient memory.

Definition at line 177 of file [exceptions](#).

The documentation for this class was generated from the following file:


- [l4/cxx/exceptions](#)

## 15.176 L4::Pager Class Reference


[Pager](#) interface including the [io\\_pager](#) interface.

```
#include <pager>
```

Inheritance diagram for L4::Pager:



Collaboration diagram for L4::Pager:



### Public Member Functions

- `l4_msgtag_t page_fault` (`l4_umword_t pfa`, `l4_umword_t pc`, `L4::lpc::Rcv_fpage rwin`, `L4::lpc::Opt< L4::lpc::Snd_fpage & > fp`)

*Page-fault protocol message.*

### Public Member Functions inherited from L4::io\_pager

- `l4_msgtag_t io_page_fault` (`l4_fpage_t io_pfa`, `l4_umword_t pc`, `L4::lpc::Rcv_fpage rwin`, `L4::lpc::Opt< L4::lpc::Snd_fpage & > fp`)

*IO page fault protocol message.*

### Additional Inherited Members

### Protected Types inherited from

**L4::Kobject\_t< Pager, io\_pager, L4\_PROTO\_PAGE\_FAULT >**

- typedef `Pager` **Class**

The target interface type (inheriting from [Kobject\\_t](#)).

- typedef Typeid::Iface< PROTO, [Pager](#) > \_\_Iface

The interface description for the derived class.

- typedef Typeid::Merge\_list< Typeid::Iface\_list< \_\_Iface >, typename lo\_pager::\_\_Iface\_list > \_\_Iface\_list

The list of all RPC interfaces provided directly or through inheritance.

## Protected Member Functions inherited from [L4::Kobject\\_t< Pager, lo\\_pager, L4\\_PROTO\\_PAGE\\_FAULT >](#)

- [L4::Cap< Class > c \(\)](#) const noexcept

Get the capability to ourselves.

## Static Protected Member Functions inherited from [L4::Kobject\\_t< Pager, lo\\_pager, L4\\_PROTO\\_PAGE\\_FAULT >](#)

- static void [\\_\\_check\\_protocols\\_\\_ \(\)](#) noexcept

Helper to check for protocol conflicts.

### 15.176.1 Detailed Description

[Pager](#) interface including the [lo\\_pager](#) interface.

This class defines the interface for handling page fault IPC. If a thread causes a page fault, the microkernel synthesises a page fault IPC message and sends it to the thread's page fault handler (pager). The pager can then handle the message, for example by establishing a suitable page mapping.

The page fault handler is set with the [L4::Thread::control](#) interface.

Definition at line 87 of file [pager](#).

### 15.176.2 Member Function Documentation

#### 15.176.2.1 [page\\_fault\(\)](#)

```
l4_msgtag_t L4::Pager::page_fault (
    l4_umword_t pfa,
    l4_umword_t pc,
    L4::Ipc::Rcv_fpage rwin,
    L4::Ipc::Opt< L4::Ipc::Snd_fpage & > fp)
```

Page-fault protocol message.

#### Parameters

<i>pfa</i>	Faulting address including failure reason: bits [0:2].
<i>pc</i>	Faulting program counter.
<i>rwin</i>	Receive window for a flexpage mapping resolving the page fault.

out	fp	Optional: flexpage descriptor to send to the task raising the page fault.
-----	----	---

### Returns

System call message tag; use [l4\\_error\(\)](#) to check for errors.

Page-fault messages are usually generated by the kernel and need to be handled by an appropriate handler function, potentially filling in `fp` for the reply.

`pfa` encoding is as shown:

[63/31 .. 3]	2	1	0
PFA	X	W	r

- **PFA** Bits 63/31..3 of `pfa` are the page fault address bits 63/31 to 3, bits 2..0 are masked.
- **X** Bit 2 of `pfa` if set, indicates a page fault during instruction fetch. Note, this bit is implementation-defined and might always be clear. Therefore, if this bit is clear it does not imply that the page fault is not due to an instruction fetch.
- **W** Bit 1 of `pfa` is set to 1 for a page fault due to a write operation.
- **r** Bit0: reserved, undefined.

The documentation for this class was generated from the following file:

- [l4/sys/pager](#)


## 15.177 L4::Platform\_control Class Reference

[L4](#) C++ interface for controlling platform-wide properties, see [Platform Control C API](#) for the C interface.


```
#include <platform_control>
```



Inheritance diagram for L4::Platform\_control:



Collaboration diagram for L4::Platform\_control:



## Public Member Functions

- [l4\\_msgtag\\_t system\\_suspend \(l4\\_umword\\_t extras\)](#)  
*Enter suspend to RAM.*
- [l4\\_msgtag\\_t system\\_shutdown \(l4\\_umword\\_t reboot\)](#)  
*Shutdown/Reboot the system.*
- [l4\\_msgtag\\_t cpu\\_allow\\_shutdown \(l4\\_umword\\_t phys\\_id, l4\\_umword\\_t enable\)](#)  
*Allow CPU shutdown.*
- [l4\\_msgtag\\_t cpu\\_enable \(l4\\_umword\\_t phys\\_id\)](#)  
*Enable an offline CPU.*
- [l4\\_msgtag\\_t cpu\\_disable \(l4\\_umword\\_t phys\\_id\)](#)  
*Disable an online CPU.*

## Public Member Functions inherited from [L4::Kobject](#)

- [l4\\_msgtag\\_t dec\\_refcnt](#) ([l4\\_mword\\_t diff](#), [l4\\_utcb\\_t \\*utcb=l4\\_utcb\(\)](#))  
*Decrement the in kernel reference counter for the object.*

## Additional Inherited Members

## Protected Types inherited from

[L4::Kobject\\_t](#)< [Platform\\_control](#), [Kobject](#), [L4\\_PROTO\\_PLATFORM\\_CTL](#) >

- typedef [Platform\\_control](#) **Class**  
*The target interface type (inheriting from [Kobject\\_t](#)).*
- typedef [Typeid::Iface](#)< [PROTO](#), [Platform\\_control](#) > **\_\_Iface**  
*The interface description for the derived class.*
- typedef [Typeid::Merge\\_list](#)< [Typeid::Iface\\_list](#)< **\_\_Iface** >, [typename Kobject::\\_\\_Iface\\_list](#) > **\_\_Iface\_list**  
*The list of all RPC interfaces provided directly or through inheritance.*

## Protected Member Functions inherited from

[L4::Kobject\\_t](#)< [Platform\\_control](#), [Kobject](#), [L4\\_PROTO\\_PLATFORM\\_CTL](#) >

- [L4::Cap](#)< [Class](#) > **c** () const noexcept  
*Get the capability to ourselves.*

## Protected Member Functions inherited from [L4::Kobject](#)

- [l4\\_cap\\_idx\\_t cap](#) () const noexcept  
*Return capability selector.*

## Static Protected Member Functions inherited from

[L4::Kobject\\_t](#)< [Platform\\_control](#), [Kobject](#), [L4\\_PROTO\\_PLATFORM\\_CTL](#) >

- static void **\_\_check\_protocols** () noexcept  
*Helper to check for protocol conflicts.*

### 15.177.1 Detailed Description

[L4](#) C++ interface for controlling platform-wide properties, see [Platform Control C API](#) for the C interface.

Add

```
#include <l4/sys/platform_control>
```

to your code to use the platform control functions. The API allows a client to suspend, reboot or shutdown the system.

For the C interface refer to the [Platform Control C API](#).

Definition at line 36 of file [platform\\_control](#).

## 15.177.2 Member Function Documentation

### 15.177.2.1 `cpu_allow_shutdown()`

```
l4_msgtag_t L4::Platform_control::cpu_allow_shutdown (
    l4_umword_t phys_id,
    l4_umword_t enable)
```

Allow CPU shutdown.

#### Parameters


<i>phys_id</i>	Physical CPU id of CPU (e.g. local APIC id) to disable.
<i>enable</i>	Allow shutdown when 1, disallow when 0.

Sets or unsets a hint that a CPU that is not currently used may be powered down.

References [L4\\_PLATFORM\\_CTL\\_CPU\\_ENABLE\\_OP](#).

Referenced by [system\\_shutdown\(\)](#).

Here is the caller graph for this function:



### 15.177.2.2 `cpu_disable()`

```
l4_msgtag_t L4::Platform_control::cpu_disable (
    l4_umword_t phys_id)
```

Disable an online CPU.

#### Parameters

<i>phys_id</i>	Physical CPU id of CPU (e.g. local APIC id) to disable.
----------------	---

**Returns**

System call message tag

This function is currently only supported on the ARM EXYNOS platform.


References [cpu\\_disable\(\)](#).

Referenced by [cpu\\_disable\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:

**15.177.2.3 cpu\_enable()**

```
l4_msgtag_t L4::Platform_control::cpu_enable (  
    l4_umword_t phys_id)
```

Enable an offline CPU.

**Parameters**

<i>phys_id</i>	Physical CPU id of CPU (e.g. local APIC id) to enable.
----------------	--

**Returns**


System call message tag

This function is currently only supported on the ARM EXYNOS platform.


References [cpu\\_enable\(\)](#), and [L4\\_PLATFORM\\_CTL\\_CPU\\_DISABLE\\_OP](#).

Referenced by [cpu\\_enable\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:

**15.177.2.4 system\_shutdown()**

```
l4_msgtag_t L4::Platform_control::system_shutdown (
    l4_umword_t reboot)
```

Shutdown/Reboot the system.


**Parameters**

<i>reboot</i>	1 for reboot, 0 for power off
---------------	-------------------------------


References [cpu\\_allow\\_shutdown\(\)](#), [L4\\_PLATFORM\\_CTL\\_CPU\\_ALLOW\\_SHUTDOWN\\_OP](#), and [system\\_shutdown\(\)](#).

Referenced by [system\\_shutdown\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 15.177.2.5 system\_suspend()

```
l4_msgtag_t L4::Platform_control::system_suspend (
    l4_umword_t extras)
```

Enter suspend to RAM.

#### Precondition

Must only be invoked on the boot CPU. Furthermore it must be ensured that the invoking thread is not migrated to a different CPU during the suspend.


#### Parameters

<i>extras</i>	Some extra platform-specific information needed to enter suspend to RAM. On x86 platforms and when using the <a href="#">Platform_control</a> object provided by Fiasco, the value defines the sleep state. The sleep states are defined in the ACPI table. Other platforms as well as lo's <a href="#">Platform_control</a> object don't make use of this value at the moment.
---------------	---


References [L4\\_PLATFORM\\_CTL\\_SYS\\_SHUTDOWN\\_OP](#), and [system\\_suspend\(\)](#).

Referenced by [system\\_suspend\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



The documentation for this class was generated from the following file:

- [l4/sys/platform\\_control](#)


## 15.178 L4::Poll\_timeout\_counter Class Reference

Evaluate an expression for a maximum number of times.

```
#include <poll_timeout_counter.h>
```



Collaboration diagram for L4::Poll\_timeout\_counter:



## Public Member Functions

- [Poll\\_timeout\\_counter](#) (unsigned counter\_val)  
*Constructor.*
- void [set](#) (unsigned counter\_val)  
*Set the counter to a certain value.*
- bool [test](#) (bool expression=true)  
*Evaluate the expression for a maximum number of times.*
- bool [timed\\_out](#) () const  
*Indicator if the maximum number of tests was required.*

### 15.178.1 Detailed Description

Evaluate an expression for a maximum number of times.

A typical use case is testing for a bit change in a hardware register for a maximum number of times (polling). For example:

```
Mmio_register_block regs;
Poll_timeout_counter i(3000000);
while (i.test(!(regs.read<l4_uint32_t>(0x04) & 1)))
;
```

The following usage is **wrong**:

```
...
Poll_timeout_counter i(3000000);
while (!i.test((regs.read<l4_uint32_t>(0x04) & 1)))
;
```

This loop would never terminate if the hardware register doesn't change!

Definition at line 34 of file [poll\\_timeout\\_counter.h](#).

## 15.178.2 Constructor & Destructor Documentation

### 15.178.2.1 Poll\_timeout\_counter()

```
L4::Poll_timeout_counter::Poll_timeout_counter (
    unsigned counter_val) [inline]
```

Constructor.


#### Parameters

<i>counter_val</i>	Maximum number of times to repeat the test.
--------------------	---

Definition at line 42 of file [poll\\_timeout\\_counter.h](#).

References [set\(\)](#).

Here is the call graph for this function:



## 15.178.3 Member Function Documentation

### 15.178.3.1 set()

```
void L4::Poll_timeout_counter::set (
    unsigned counter_val) [inline]
```

Set the counter to a certain value.


#### Parameters

<i>counter_val</i>	New counter value for maximum number of times to repeat the test.
--------------------	---

Definition at line 53 of file [poll\\_timeout\\_counter.h](#).

Referenced by [Poll\\_timeout\\_counter\(\)](#).

Here is the caller graph for this function:



### 15.178.3.2 timed\_out()

```
bool L4::Poll_timeout_counter::timed_out () const [inline]
```

Indicator if the maximum number of tests was required.

#### Return values

<i>true, if</i>	the maximum number of tests was required or if the counter was initialized to zero.
-----------------	---

Definition at line 81 of file [poll\\_timeout\\_counter.h](#).

The documentation for this class was generated from the following file:


- [pkg/drivers-frst/include/poll\\_timeout\\_counter.h](#)

## 15.179 L4::Poll\_timeout\_kipclock Class Reference

A polling timeout based on the [L4Re](#) clock.

```
#include <poll_timeout_kipclock>
```

Collaboration diagram for L4::Poll\_timeout\_kipclock:



#### Public Member Functions

- [Poll\\_timeout\\_kipclock](#) (unsigned poll\_time\_us)  
*Initialise relative timeout in microseconds.*
- void [set](#) (unsigned poll\_time\_us)  
*(Re-)Set relative timeout in microseconds*
- bool [test](#) (bool expression=true)  
*Test whether timeout has expired.*
- bool [timed\\_out](#) () const  
*Query whether timeout has expired.*

### 15.179.1 Detailed Description

A polling timeout based on the [L4Re](#) clock.

This class allows to conveniently add a timeout to a polling loop.

The original

```
while (device.read(State) & Busy)
;
```

is converted to

```
Poll_timeout_kipclock timeout(10000);
while (timeout.test(device.read(State) & Busy))
;
if (timeout.timed_out())
    printf("ERROR: Device does not respond.\n");
```

Definition at line 35 of file [poll\\_timeout\\_kipclock](#).

### 15.179.2 Constructor & Destructor Documentation

#### 15.179.2.1 Poll\_timeout\_kipclock()

```
L4::Poll_timeout_kipclock::Poll_timeout_kipclock (
    unsigned poll_time_us) [inline]
```

Initialise relative timeout in microseconds.

#### Parameters

<i>poll_time_us</i>	Polling timeout in microseconds.
---------------------	----------------------------------

Definition at line 42 of file [poll\\_timeout\\_kipclock](#).

References [set\(\)](#).

Here is the call graph for this function:



### 15.179.3 Member Function Documentation

#### 15.179.3.1 set()

```
void L4::Poll_timeout_kipclock::set (
    unsigned poll_time_us) [inline]
```

(Re-)Set relative timeout in microseconds

##### Parameters


<i>poll_time_us</i>	Polling timeout in microseconds.
---------------------	----------------------------------

Definition at line 51 of file [poll\\_timeout\\_kipclock](#).


References [l4\\_kip\\_clock\(\)](#), and [l4re\\_kip\(\)](#).

Referenced by [Poll\\_timeout\\_kipclock\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



#### 15.179.3.2 test()

```
bool L4::Poll_timeout_kipclock::test (
    bool expression = true) [inline]
```

Test whether timeout has expired.

### Parameters

<i>expression</i>	Optional expression.
-------------------	----------------------


### Return values

<i>false</i>	The timeout has expired or the given expression returned false.
<i>true</i>	The timeout has not expired and the optionally given expression returns true.

Definition at line 65 of file [poll\\_timeout\\_kipclock](#).

References [l4\\_kip\\_clock\(\)](#), and [l4re\\_kip\(\)](#).

Here is the call graph for this function:



### 15.179.3.3 timed\_out()

```
bool L4::Poll_timeout_kipclock::timed_out () const [inline]
```

Query whether timeout has expired.

#### Returns

Expiry state of timeout

Definition at line 77 of file [poll\\_timeout\\_kipclock](#).

The documentation for this class was generated from the following file:


- `l4/re/util/poll_timeout_kipclock`

## 15.180 L4::Proto\_t< P > Struct Template Reference

Data type for defining protocol numbers.

```
#include <__typeinfo.h>
```

Collaboration diagram for L4::Proto\_t< P >:



### 15.180.1 Detailed Description

```
template<I4\_proto\_t P = PROTO_EMPTY>
struct L4::Proto_t< P >
```

Data type for defining protocol numbers.

#### Template Parameters

<i>P</i>	The protocol number itself
----------	----------------------------

This type must be used when specifying a protocol number with [Kobject\\_x](#).

Definition at line [1181](#) of file [\\_\\_typeinfo.h](#).

The documentation for this struct was generated from the following file:


- [I4/sys/\\_\\_typeinfo.h](#)

## 15.181 L4::Rcv\_endpoint Class Reference

Interface for kernel objects that allow to receive IPC from them.


```
#include <rcv_endpoint>
```

Inheritance diagram for L4::Rcv\_endpoint:





Collaboration diagram for L4::Rcv\_endpoint:



## Public Member Functions

- `l4_msgtag_t bind_thread (lpc::Cap< Thread > t, l4_umword_t label)`  
*Bind the IPC receive endpoint to a thread.*
- `l4_msgtag_t bind_snd_destination (Cap< Snd_destination > snd_dst, l4_umword_t label)`  
*Bind a send destination (a thread or thread group) to an IPC receive endpoint.*

## Public Member Functions inherited from L4::Kobject

- `l4_msgtag_t dec_refcnt (l4_mword_t diff, l4_utcb_t *utcb=l4_utcb())`  
*Decrement the in kernel reference counter for the object.*

## Additional Inherited Members

### Protected Types inherited from

[L4::Kobject\\_t< Rcv\\_endpoint, Kobject, L4\\_PROTO\\_KOBJECT, Type\\_info::Demand\\_t< 1 > >](#)

- typedef [Rcv\\_endpoint](#) **Class**  
*The target interface type (inheriting from [Kobject\\_t](#)).*
- typedef Typeid::Iface< PROTO, [Rcv\\_endpoint](#) > **\_\_Iface**  
*The interface description for the derived class.*
- typedef Typeid::Merge\_list< Typeid::Iface\_list< **\_\_Iface** >, typename Kobject::\_\_Iface\_list > **\_\_Iface\_list**  
*The list of all RPC interfaces provided directly or through inheritance.*

### Protected Member Functions inherited from

[L4::Kobject\\_t< Rcv\\_endpoint, Kobject, L4\\_PROTO\\_KOBJECT, Type\\_info::Demand\\_t< 1 > >](#)

- [L4::Cap< Class > c](#) () const noexcept  
*Get the capability to ourselves.*

### Protected Member Functions inherited from [L4::Kobject](#)

- [l4\\_cap\\_idx\\_t](#) [cap](#) () const noexcept  
*Return capability selector.*

### Static Protected Member Functions inherited from

[L4::Kobject\\_t< Rcv\\_endpoint, Kobject, L4\\_PROTO\\_KOBJECT, Type\\_info::Demand\\_t< 1 > >](#)

- static void [\\_\\_check\\_protocols\\_\\_](#) () noexcept  
*Helper to check for protocol conflicts.*

## 15.181.1 Detailed Description

Interface for kernel objects that allow to receive IPC from them.

Such an object is for example an [lpc\\_gate](#) (with server rights) or an [lrq](#). Those objects can be bound to a thread that shall receive IPC from these objects via [bind\\_thread\(\)](#) or [bind\\_snd\\_destination\(\)](#).

Definition at line 30 of file [rcv\\_endpoint](#).

## 15.181.2 Member Function Documentation

### 15.181.2.1 bind\_snd\_destination()

```
l4_msgtag_t L4::Rcv_endpoint::bind_snd_destination (
    Cap< Snd_destination > snd_dst,
    l4_umword_t label) [inline]
```

Bind a send destination (a thread or thread group) to an IPC receive endpoint.

#### Parameters

<i>snd_dst</i>	Snd_destination object (a thread or thread group) that shall be bound to this receive endpoint. See <a href="#">bind_thread()</a> and <a href="#">bind_snd_destination()</a> for binding a thread or thread group object.
<i>label</i>	Label to assign to this receive endpoint. For IPC gates, the two least significant bits must be set to zero.

#### Returns

Syscall return tag containing one of the following return codes.

#### Return values

<i>L4_EOK</i>	Operation successful.
<i>-L4_EINVAL</i>	snd_dst is not a thread or thread group object or other arguments were malformed.
<i>-L4_EPERM</i>	No <a href="#">L4_CAP_FPAGE_S</a> right on snd_dst or the capability used to invoke this operation.

#### Precondition


If this operation is invoked using an IPC gate capability without the [L4\\_FPAGE\\_C\\_IPCGATE\\_SVR](#) right, the kernel will not perform the operation. Instead, the underlying IPC message will be forwarded to the thread bound to the IPC gate, blocking the caller if no thread or thread group is bound yet.

The specified *label* is passed to the receiver of the incoming IPC. It is possible to re-bind a receive endpoint to the same or a different thread or thread group. In this case, IPC already in flight will be delivered with the old label to the previously bound thread or thread group unless [L4::Thread::modify\\_senders\(\)](#) is used to change these labels.

Definition at line 101 of file [rcv\\_endpoint](#).

References [L4::Cap\\_base::cap\(\)](#), [L4::Kobject::cap\(\)](#), and [l4\\_rcv\\_ep\\_bind\\_snd\\_destination\(\)](#).

Here is the call graph for this function:



### 15.181.2.2 `bind_thread()`

```
l4_msgtag_t L4::Rcv_endpoint::bind_thread (
    ipc::Cap< Thread > t,
    l4_umword_t label)
```

Bind the IPC receive endpoint to a thread.

#### Parameters

<i>t</i>	<a href="#">Thread</a> object this receive endpoint shall be bound to.
<i>label</i>	Label to assign to <code>this</code> receive endpoint. For IPC gates, the two least significant bits must be set to zero.

#### Returns

Syscall return tag containing one of the following return codes.

#### Return values

<i>L4_EOK</i>	Operation successful.
<i>-L4_EINVAL</i>	<i>t</i> is not a thread object or other arguments were malformed.
<i>-L4_EPERM</i>	Insufficient permissions; see precondition.

#### Precondition

The invoked capability and the capability *t* both must have the permission [L4\\_CAP\\_FPAGE\\_S](#).

**Deprecated** Use [bind\\_snd\\_destination\(\)](#) instead.

#### Precondition


If this operation is invoked using an IPC gate capability without the [L4\\_FPAGE\\_C\\_IPCGATE\\_SVR](#) right, the kernel will not perform the operation. Instead, the underlying IPC message will be forwarded to the thread the IPC gate is bound to, blocking the caller if the IPC gate was not bound yet.

The specified *label* is passed to the receiver of the incoming IPC. It is possible to re-bind a receive endpoint to the same or a different thread. In this case, IPC already in flight will be delivered with the old label to the previously bound thread unless [L4::Thread::modify\\_senders\(\)](#) is used to change these labels.


References [bind\\_thread\(\)](#).

Referenced by [bind\\_thread\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



The documentation for this class was generated from the following file:


- `l4/sys/rcv_endpoint`

## 15.182 L4::Registry\_iface Class Reference

Abstract interface for object registries.

```
#include <ipc_epiface>
```

Inheritance diagram for L4::Registry\_iface:



Collaboration diagram for L4::Registry\_iface:



## Public Member Functions

- virtual [L4::Cap< void >](#) [register\\_obj](#) ([L4::Epiface](#) \*o, char const \*service)=0  
*Register an [L4::Epiface](#) for an IPC gate available in the applications environment under the name `service`.*
- virtual [L4::Cap< void >](#) [register\\_obj](#) ([L4::Epiface](#) \*o)=0  
*Register o as server-side object for synchronous RPC.*
- virtual [L4::Cap< L4::Irq >](#) [register\\_irq\\_obj](#) ([L4::Epiface](#) \*o)=0  
*Register o as server-side object for asynchronous IRQs.*
- virtual [L4::Cap< L4::Rcv\\_endpoint >](#) [register\\_obj](#) ([L4::Epiface](#) \*o, [L4::Cap< L4::Rcv\\_endpoint >](#) ep)=0  
*Register o as server-side object for a pre-allocated capability.*
- virtual void [unregister\\_obj](#) ([L4::Epiface](#) \*o, bool unmap=true)=0  
*Unregister the given object o from the server.*

### 15.182.1 Detailed Description

Abstract interface for object registries.

An object registry allows to register [L4::Epiface](#) objects at a server loop either for synchronous RPC messages or for asynchronous IRQ messages.

Definition at line 322 of file [ipc\\_epiface](#).

### 15.182.2 Member Function Documentation

#### 15.182.2.1 [register\\_irq\\_obj\(\)](#)

```
virtual L4::Cap< L4::Irq > L4::Registry\_iface::register\_irq\_obj (  
    L4::Epiface * o) [pure virtual]
```

Register o as server-side object for asynchronous IRQs.

#### Parameters

<a href="#">o</a>	Pointer to an <a href="#">Epiface</a> object that shall be registered as server-side object for IRQs.
-------------------	---

#### Return values

<a href="#">L4::Cap&lt;L4::Irq&gt;</a>	Capability to a new IRQ object on success.
<a href="#">L4::Cap&lt;L4::Irq&gt;::Invalid</a>	The allocation of the IRQ has failed.

After successful registration `o->obj_cap()` will be the capability of the allocated IRQ object.

The function may allocate a capability slot for the object. In that case [unregister\\_obj\(\)](#) is responsible for freeing the slot as well.

Implemented in [L4Re::Util::Object\\_registry](#).

**15.182.2.2 register\_obj() [1/3]**

```
virtual L4::Cap< void > L4::Registry_iface::register_obj (
    L4::Epiface * o) [pure virtual]
```

Register *o* as server-side object for synchronous RPC.

**Parameters**

<i>o</i>	Pointer to an <a href="#">Epiface</a> object that shall be registered as server-side object for RPC.
----------	--

**Return values**

<a href="#">L4::Cap&lt; void &gt;</a>	A valid capability to a new IPC gate.
<a href="#">L4::Cap&lt; void &gt;::Invalid</a>	The allocation of the IPC gate has failed.

After successful registration *o*→*obj\_cap()* will be the capability of the allocated IPC gate.

The function may allocate a capability slot for the object. In that case [unregister\\_obj\(\)](#) is responsible for freeing the slot as well.

Implemented in [L4Re::Util::Object\\_registry](#).

**15.182.2.3 register\_obj() [2/3]**

```
virtual L4::Cap< void > L4::Registry_iface::register_obj (
    L4::Epiface * o,
    char const * service) [pure virtual]
```

Register an [L4::Epiface](#) for an IPC gate available in the applications environment under the name *service*.

**Parameters**

<i>o</i>	Pointer to an <a href="#">Epiface</a> object that shall be registered.
<i>service</i>	Name of the capability that shall be used to connect <i>o</i> to as a server-side object.

**Return values**

<a href="#">L4::Cap&lt; void &gt;</a>	The capability known as <i>service</i> on success.
<a href="#">L4::Cap&lt; void &gt;::Invalid</a>	No capability with the given name found.

After a successful call to this function *o*→*obj\_cap()* is equal to the capability in the environment with the name given by *service*.

Implemented in [L4Re::Util::Object\\_registry](#).



**15.182.2.4 register\_obj()** [3/3]

```
virtual L4::Cap< L4::Rcv_endpoint > L4::Registry_iface::register_obj (
    L4::Epiface * o,
    L4::Cap< L4::Rcv_endpoint > ep) [pure virtual]
```

Register *o* as server-side object for a pre-allocated capability.

**Parameters**

<i>o</i>	Pointer to an <a href="#">Epiface</a> object that shall be registered as server-side object.
<i>ep</i>	Capability to an already allocated capability where <i>o</i> shall be attached as server-side handler. The capability may point to an IPC gate or an IRQ.

**Return values**

<a href="#">L4::Cap&lt;L4::Rcv_endpoint&gt;</a>	Capability <i>ep</i> on success.
<a href="#">L4::Cap&lt;L4::Rcv_endpoint&gt;::Invalid</a>	The IRQ attach operation has failed.

After successful registration *o*→*obj\_cap()* will be equal to *ep*.

Implemented in [L4Re::Util::Object\\_registry](#).

**15.182.2.5 unregister\_obj()**

```
virtual void L4::Registry_iface::unregister_obj (
    L4::Epiface * o,
    bool unmap = true) [pure virtual]
```

Unregister the given object *o* from the server.

**Parameters**

<i>o</i>	Pointer to the <a href="#">Epiface</a> object that shall be unregistered. The object must have been registered with any of the register methods if <a href="#">Registry_iface</a> .
<i>unmap</i>	If true the capability <i>o</i> → <i>obj_cap()</i> shall be unmapped from the local object space.

The function always unmaps and frees the capability if it was allocated by either [Registry\\_iface::register\\_irq\\_obj\(L4::Epiface \\*\)](#), or by [Registry\\_iface::register\\_obj\(L4::Epiface \\*\)](#).

Implemented in [L4Re::Util::Object\\_registry](#).

The documentation for this class was generated from the following file:


- `l4/sys/cxx/ipc_epiface`

## 15.183 L4::Runtime\_error Class Reference


[Exception](#) for an abstract runtime error.

```
#include <l4/cxx/exceptions>
```

Inheritance diagram for L4::Runtime\_error:



Collaboration diagram for L4::Runtime\_error:



## Public Member Functions

- [Runtime\\_error](#) (long [err\\_no](#), char const \*extra=0) noexcept  
*Create a new [Runtime\\_error](#).*
- char const \* [str](#) () const noexcept override  
*Return a human readable string for the exception.*
- char const \* [extra\\_str](#) () const  
*Get the description text for this runtime error.*
- long [err\\_no](#) () const noexcept  
*Get the error value for this runtime error.*

## Public Member Functions inherited from [L4::Base\\_exception](#)

- virtual ~[Base\\_exception](#) () noexcept  
*Destruction.*

## Public Member Functions inherited from [L4::Exception\\_tracer](#)

- void const \*const \* **pc\_array** () const noexcept  
*Get the array containing the call trace.*
- int **frame\_count** () const noexcept  
*Get the number of entries that are valid in the call trace.*

## Additional Inherited Members

## Protected Member Functions inherited from [L4::Base\\_exception](#)

- **Base\_exception** () noexcept  
*Create a base exception.*

## Protected Member Functions inherited from [L4::Exception\\_tracer](#)

- **Exception\_tracer** () noexcept  
*Create a back trace.*

### 15.183.1 Detailed Description

[Exception](#) for an abstract runtime error.

This is the base class for a set of exceptions that cover all errors that have a C error value (see [l4\\_error\\_code\\_t](#)).

Definition at line [128](#) of file [exceptions](#).

### 15.183.2 Constructor & Destructor Documentation

#### 15.183.2.1 Runtime\_error()

```
L4::Runtime_error::Runtime_error (
    long err_no,
    char const * extra = 0) [inline], [explicit], [noexcept]
```

Create a new [Runtime\\_error](#).

#### Parameters


<i>err_no</i>	Error value for this runtime error.
<i>extra</i>	Description of what happened when the error occurred.

Definition at line [141](#) of file [exceptions](#).


References [err\\_no\(\)](#).

Referenced by [L4::Out\\_of\\_memory::Out\\_of\\_memory\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 15.183.3 Member Function Documentation

#### 15.183.3.1 `err_no()`

```
long L4::Runtime_error::err_no () const [inline], [noexcept]
```

Get the error value for this runtime error.


##### Returns

Error value.

Definition at line 170 of file [exceptions](#).

Referenced by [Runtime\\_error\(\)](#).

Here is the caller graph for this function:



### 15.183.3.2 `extra_str()`

```
char const * L4::Runtime_error::extra_str () const [inline]
```

Get the description text for this runtime error.

#### Returns

Pointer to the description string.

Definition at line [162](#) of file [exceptions](#).

The documentation for this class was generated from the following file:


- [l4/cxx/exceptions](#)

## 15.184 L4::Scheduler Class Reference


C++ interface of the [Scheduler](#) kernel object, see [Scheduler](#) for the C interface.

```
#include <scheduler>
```

Inheritance diagram for L4::Scheduler:



Collaboration diagram for L4::Scheduler:



## Public Member Functions

- `l4_msgtag_t info (l4_umword_t *cpu_max, l4_sched_cpu_set_t *cpus, l4_umword_t *sched_classes=nullptr, l4_utcb_t *utcb=l4_utcb()) const noexcept`  
Get scheduler information.
- `l4_msgtag_t run_thread (lpc::Cap< Thread > thread, l4_sched_param_t const &sp)`  
Run a thread on a *Scheduler*.



- [l4\\_msgtag\\_t idle\\_time](#) ([l4\\_sched\\_cpu\\_set\\_t](#) const &cpus, [l4\\_kernel\\_clock\\_t](#) \*us)  
*Query the idle time (in  $\mu$ s) of a CPU.*
- [bool is\\_online](#) ([l4\\_umword\\_t](#) cpu, [l4\\_utcb\\_t](#) \*utcb=[l4\\_utcb\(\)](#)) const noexcept  
*Query if a CPU is online.*

## Public Member Functions inherited from [L4::lcu](#)

- [l4\\_msgtag\\_t bind](#) (unsigned irqnum, [L4::Cap](#)< [Triggerable](#) > irq, [l4\\_utcb\\_t](#) \*utcb=[l4\\_utcb\(\)](#)) noexcept  
*Bind an interrupt line of an interrupt controller to an interrupt object.*
- [l4\\_msgtag\\_t unbind](#) (unsigned irqnum, [L4::Cap](#)< [Triggerable](#) > irq, [l4\\_utcb\\_t](#) \*utcb=[l4\\_utcb\(\)](#)) noexcept  
*Remove binding of an interrupt line from the interrupt controller object.*
- [l4\\_msgtag\\_t info](#) ([l4\\_icu\\_info\\_t](#) \*info, [l4\\_utcb\\_t](#) \*utcb=[l4\\_utcb\(\)](#)) noexcept  
*Get information about the ICU features.*
- [l4\\_msgtag\\_t msi\\_info](#) ([l4\\_umword\\_t](#) irqnum, [l4\\_uint64\\_t](#) source, [l4\\_icu\\_msi\\_info\\_t](#) \*msi\_info)  
*Get MSI info about IRQ.*
- [l4\\_msgtag\\_t mask](#) (unsigned irqnum, [l4\\_umword\\_t](#) \*label=0, [l4\\_timeout\\_t](#) to=[L4\\_IPC\\_NEVER](#), [l4\\_utcb\\_t](#) \*utcb=[l4\\_utcb\(\)](#)) noexcept  
*Mask an IRQ line.*
- [l4\\_msgtag\\_t set\\_mode](#) (unsigned irqnum, [l4\\_umword\\_t](#) mode, [l4\\_utcb\\_t](#) \*utcb=[l4\\_utcb\(\)](#)) noexcept  
*Set interrupt mode.*

## Public Member Functions inherited from [L4::lrq\\_eoi](#)

- [l4\\_msgtag\\_t unmask](#) (unsigned irqnum, [l4\\_umword\\_t](#) \*label=0, [l4\\_timeout\\_t](#) to=[L4\\_IPC\\_NEVER](#), [l4\\_utcb\\_t](#) \*utcb=[l4\\_utcb\(\)](#)) noexcept  
*Unmask the given interrupt line.*

## Additional Inherited Members

## Protected Types inherited from

[L4::Kobject\\_t](#)< [Scheduler](#), [lcu](#), [L4\\_PROTO\\_SCHEDULER](#), [Type\\_info::Demand\\_t](#)< 1 > >

- typedef [Scheduler](#) **Class**  
*The target interface type (inheriting from [Kobject\\_t](#)).*
- typedef [Typeid::Iface](#)< [PROTO](#), [Scheduler](#) > **\_\_iface**  
*The interface description for the derived class.*
- typedef [Typeid::Merge\\_list](#)< [Typeid::Iface\\_list](#)< **\_\_iface** >, typename [lcu](#)::[\\_\\_iface\\_list](#) > **\_\_iface\_list**  
*The list of all RPC interfaces provided directly or through inheritance.*

## Protected Types inherited from

[L4::Kobject\\_t](#)< [lcu](#), [lrq\\_eoi](#), [L4\\_PROTO\\_IRQ](#), [Type\\_info::Demand\\_t](#)< 1 > >

- typedef [lcu](#) **Class**  
*The target interface type (inheriting from [Kobject\\_t](#)).*
- typedef [Typeid::Iface](#)< [PROTO](#), [lcu](#) > **\_\_iface**  
*The interface description for the derived class.*
- typedef [Typeid::Merge\\_list](#)< [Typeid::Iface\\_list](#)< **\_\_iface** >, typename [lrq\\_eoi](#)::[\\_\\_iface\\_list](#) > **\_\_iface\_list**  
*The list of all RPC interfaces provided directly or through inheritance.*

**Protected Member Functions inherited from****[L4::Kobject\\_t< Scheduler, Icu, L4\\_PROTO\\_SCHEDULER, Type\\_info::Demand\\_t< 1 > >](#)**

- [L4::Cap< Class > c \(\)](#) const noexcept

*Get the capability to ourselves.***Protected Member Functions inherited from****[L4::Kobject\\_t< Icu, Irq\\_eoi, L4\\_PROTO\\_IRQ, Type\\_info::Demand\\_t< 1 > >](#)**

- [L4::Cap< Class > c \(\)](#) const noexcept

*Get the capability to ourselves.***Static Protected Member Functions inherited from****[L4::Kobject\\_t< Scheduler, Icu, L4\\_PROTO\\_SCHEDULER, Type\\_info::Demand\\_t< 1 > >](#)**

- static void [\\_\\_check\\_protocols\\_\\_ \(\)](#) noexcept

*Helper to check for protocol conflicts.***Static Protected Member Functions inherited from****[L4::Kobject\\_t< Icu, Irq\\_eoi, L4\\_PROTO\\_IRQ, Type\\_info::Demand\\_t< 1 > >](#)**

- static void [\\_\\_check\\_protocols\\_\\_ \(\)](#) noexcept

*Helper to check for protocol conflicts.***15.184.1 Detailed Description**

C++ interface of the [Scheduler](#) kernel object, see [Scheduler](#) for the C interface.

The [Scheduler](#) interface allows a client to manage CPU resources. The API provides functions to query scheduler information, check the online state of CPUs, query CPU idle time and to start threads on defined CPU sets.

The scheduler offers IRQ number 0, which triggers when the number of online cores changes, e.g. due to hotplug events.

The [Scheduler](#) interface inherits from [L4::Icu](#) and [L4::Irq\\_eoi](#) for managing the scheduler virtual device IRQ which, in contrast to hardware IRQs, implements a limited functionality:

- Only IRQ line 0 is supported, no MSI vectors.
- The IRQ is edge-triggered and the IRQ mode cannot be changed.
- As the IRQ is edge-triggered, it does not have to be explicitly unmasked.

It depends on the platform, which hotplug events actually trigger the IRQ. Many platforms only support triggering the IRQ when a CPU core different from the boot CPU goes online.

**Include File**

```
#include <l4/sys/scheduler>
```

Definition at line 46 of file [scheduler](#).

## 15.184.2 Member Function Documentation

### 15.184.2.1 idle\_time()

```
l4_msgtag_t L4::Scheduler::idle_time (
    l4_sched_cpu_set_t const & cpus,
    l4_kernel_clock_t * us)
```

Query the idle time (in  $\mu$ s) of a CPU.

#### Parameters

	<i>cpus</i>	Set of CPUs to query. Only the idle time of the first selected CPU in <code>cpus.map</code> is queried.
out	<i>us</i>	Idle time of queried CPU in $\mu$ s.

#### Return values

<i>0</i>	Success.
<i>-L4_EINVAL</i>	Invalid CPU requested in cpu set.

This function retrieves the idle time in  $\mu$ s of the first selected CPU in `cpus.map`. The idle time is the accumulated time a CPU has spent in the idle thread since its last reset. To calculate a load estimate  $l$  one has to retrieve the idle time at the beginning ( $i1$ ) and the end ( $i2$ ) of a known time interval  $t$ . The load is then calculated as  $l = 1 - (i2 - i1)/t$ .


The idle time is only defined for online CPUs. Reading the idle time from offline CPUs is undefined and may result in either getting `-L4_EINVAL` or calculating an estimated (incorrect) load of 1.

#### Note

The idle time statistics of remote CPUs is updated on context switch events only, hence may not be up-to-date when requested cross-CPU. To get up-to-date idle time you should use a thread running on the same CPU of which the idle time is requested.

Referenced by [run\\_thread\(\)](#).

Here is the caller graph for this function:



### 15.184.2.2 info()

```
l4_msgtag_t L4::Scheduler::info (
    l4_umword_t * cpu_max,
    l4_sched_cpu_set_t * cpus,
    l4_umword_t * sched_classes = nullptr,
    l4_utcb_t * utcb = l4_utcb()) const [inline], [noexcept]
```

Get scheduler information.

#### Parameters

out	<i>cpu_max</i>	Maximum number of CPUs ever available. Optional, can be nullptr.
in, out	<i>cpus</i>	<i>cpus.offset</i> is first CPU of interest. <i>cpus.granularity</i> (see <a href="#">l4_sched_cpu_set_t</a> ). <i>cpus.map</i> Bitmap of online CPUs. Must not be nullptr.
out	<i>sched_classes</i>	A bitmap of available scheduling classes (see <a href="#">L4_scheduler_classes</a> ). Pass nullptr to omit this information.
	<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. Defaults to <a href="#">l4_utcb</a> .


#### Return values

0	Success.
-L4_ERANGE	The given CPU offset is larger than the maximum number of CPUs.

Definition at line 74 of file [scheduler](#).

References [L4::Kobject\\_t< Scheduler, Icu, L4\\_PROTO\\_SCHEDULER, Type\\_info::Demand\\_t< 1 > >::c\(\)](#), [l4\\_sched\\_cpu\\_set\\_t::gran\\_offset](#), and [l4\\_sched\\_cpu\\_set\\_t::map](#).

Here is the call graph for this function:



### 15.184.2.3 is\_online()

```
bool L4::Scheduler::is_online (
    l4_umword_t cpu,
    l4_utcb_t * utcb = l4_utcb()) const [inline], [noexcept]
```

Query if a CPU is online.

**Parameters**

<i>cpu</i>	CPU number whose online status should be queried.
<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. Defaults to <a href="#">l4_utcb</a> .


**Return values**

<i>true</i>	The CPU is online.
<i>false</i>	The CPU is offline

Definition at line 154 of file [scheduler](#).

References [L4::Kobject::cap\(\)](#).

Here is the call graph for this function:

**15.184.2.4 run\_thread()**

```

l4_msgtag_t L4::Scheduler::run_thread (
    Ipc::Cap< Thread > thread,
    l4_sched_param_t const & sp)
  
```

Run a thread on a [Scheduler](#).

**Parameters**

<i>thread</i>	Capability of the thread to run.
<i>sp</i>	Scheduling parameters.

**Return values**

<i>0</i>	Success.
<i>-L4_EINVAL</i>	Invalid size of the scheduling parameter.

This function launches a thread on a CPU determined by the scheduling parameter `sp.affinity`. A thread can be intentionally stopped by migrating it on an offline or an invalid CPU. The thread is only guaranteed to run if the CPU it is migrated to is currently online.

**Note**

If the target CPU is currently not online, there is no guarantee that the thread will ever run, even if the CPU comes online later on.


A scheduler may impose a policy with regard to selecting CPUs. However the scheduler is required to ensure the following two properties:

- Two threads with disjoint CPU sets must be scheduled to different CPUs.
- Two threads with identical CPU sets selecting only a single CPU must be scheduled to the same CPU.


References [idle\\_time\(\)](#), [L4\\_SCHEDULER\\_IDLE\\_TIME\\_OP](#), and [run\\_thread\(\)](#).

Referenced by [run\\_thread\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



The documentation for this class was generated from the following file:


- [l4/sys/scheduler](#)

## 15.185 L4::Semaphore Struct Reference


C++ Kernel-provided semaphore interface, see [Kernel-provided semaphore](#) for the C interface.

```
#include <semaphore>
```

Inheritance diagram for L4::Semaphore:



Collaboration diagram for L4::Semaphore:



## Public Member Functions

- `l4_msgtag_t up (l4_utcb_t *utcb=l4_utcb()) noexcept`  
*Semaphore up operation (wrapper for `trigger()`).*
- `l4_msgtag_t down (l4_timeout_t timeout=L4_IPC_NEVER, l4_utcb_t *utcb=l4_utcb()) noexcept`  
*Semaphore down operation.*



## Public Member Functions inherited from [L4::Triggerable](#)

- [l4\\_msgtag\\_t](#) [trigger](#) ([l4\\_utcb\\_t](#) \*utcb=[l4\\_utcb\(\)](#)) noexcept  
*Trigger the object.*

## Public Member Functions inherited from [L4::Irq\\_eoi](#)

- [l4\\_msgtag\\_t](#) [unmask](#) (unsigned irqnum, [l4\\_umword\\_t](#) \*label=0, [l4\\_timeout\\_t](#) to=[L4\\_IPC\\_NEVER](#), [l4\\_utcb\\_t](#) \*utcb=[l4\\_utcb\(\)](#)) noexcept  
*Unmask the given interrupt line.*

## Additional Inherited Members

### Protected Types inherited from [L4::Kobject\\_t](#)< [Semaphore](#), [Triggerable](#), [L4\\_PROTO\\_SEMAPHORE](#) >

- typedef [Semaphore](#) **Class**  
*The target interface type (inheriting from [Kobject\\_t](#)).*
- typedef Typeid::Iface< PROTO, [Semaphore](#) > **\_\_Iface**  
*The interface description for the derived class.*
- typedef Typeid::Merge\_list< Typeid::Iface\_list< **\_\_Iface** >, typename [Triggerable](#)::\_\_Iface\_list > **\_\_Iface\_list**  
*The list of all RPC interfaces provided directly or through inheritance.*

### Protected Types inherited from [L4::Kobject\\_t](#)< [Triggerable](#), [Irq\\_eoi](#), [L4\\_PROTO\\_IRQ](#) >

- typedef [Triggerable](#) **Class**  
*The target interface type (inheriting from [Kobject\\_t](#)).*
- typedef Typeid::Iface< PROTO, [Triggerable](#) > **\_\_Iface**  
*The interface description for the derived class.*
- typedef Typeid::Merge\_list< Typeid::Iface\_list< **\_\_Iface** >, typename [Irq\\_eoi](#)::\_\_Iface\_list > **\_\_Iface\_list**  
*The list of all RPC interfaces provided directly or through inheritance.*

### Protected Member Functions inherited from [L4::Kobject\\_t](#)< [Semaphore](#), [Triggerable](#), [L4\\_PROTO\\_SEMAPHORE](#) >

- [L4::Cap](#)< [Class](#) > **c** () const noexcept  
*Get the capability to ourselves.*

### Protected Member Functions inherited from [L4::Kobject\\_t](#)< [Triggerable](#), [Irq\\_eoi](#), [L4\\_PROTO\\_IRQ](#) >

- [L4::Cap](#)< [Class](#) > **c** () const noexcept  
*Get the capability to ourselves.*

### Static Protected Member Functions inherited from

[L4::Kobject\\_t](#) < [Semaphore](#), [Triggerable](#), [L4\\_PROTO\\_SEMAPHORE](#) >

- static void `__check_protocols__()` noexcept

*Helper to check for protocol conflicts.*

### Static Protected Member Functions inherited from

[L4::Kobject\\_t](#) < [Triggerable](#), [Irq\\_eoi](#), [L4\\_PROTO\\_IRQ](#) >

- static void `__check_protocols__()` noexcept

*Helper to check for protocol conflicts.*

## 15.185.1 Detailed Description

C++ Kernel-provided semaphore interface, see [Kernel-provided semaphore](#) for the C interface.

This is the interface for kernel-provided semaphore objects. The object provides the classical functions `up()` and `down()` for counting the semaphore and blocking. The semaphore is a [Triggerable](#) with respect to the `up()` function, this means that a semaphore can be bound to an interrupt line at an ICU ([L4::lcu](#)) and incoming interrupts increment the semaphore counter.

The `down()` method decrements the semaphore counter and blocks if the counter is already zero. Blocking on a semaphore may—as all blocking operations—either return successfully, or be aborted due to an expired timeout provided to the `down()` operation, or due to an [L4::Thread::ex\\_regs\(\)](#) operation with the [L4\\_THREAD\\_EX\\_REGS\\_CANCEL](#) flag set.

A semaphore object is initialized with counter value 0.

The main reason for using a semaphore instead of an [L4::Irq](#) is to ensure that incoming trigger signals do not interfere with any open-wait operations, as used for example in a server loop.

Note that this is a kernel-level semaphore primitive that shall be used to implement user-level, application-usable synchronization primitives. For example, use `pthread_mutex` functions in applications if possible. When implementing a synchronization primitive, please ensure to only use [L4::Semaphore](#) in the case of contention, and use atomic operations for the non-contended case.

Definition at line 51 of file [semaphore](#).

## 15.185.2 Member Function Documentation

### 15.185.2.1 `down()`

```
l4_msgtag_t L4::Semaphore::down (
    l4_timeout_t timeout = L4_IPC_NEVER,
    l4_utcb_t * utcb = l4_utcb()) [inline], [noexcept]
```

[Semaphore](#) down operation.

#### Parameters

---

<i>timeout</i>	Timeout for blocking the semaphore down operation. Note: The receive timeout of this timeout-pair is significant for blocking, the send part is usually non-blocking.
<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. See <a href="#">l4_utcb</a> .

**Returns**

Syscall return tag. Use [l4\\_error\(\)](#) to check for errors.

**Return values**

<code>-L4_EPERM</code>	Insufficient permissions; see precondition.
------------------------	---

**Precondition**

The invoked [Semaphore](#) capability must have the permission [L4\\_CAP\\_FPAGE\\_S](#).

This method decrements the semaphore counter by one, or blocks if the counter is already zero, until either a timeout or cancel condition hits or the counter is increased by an [up\(\)](#) operation.

Definition at line 89 of file [semaphore](#).

References [L4::Kobject::cap\(\)](#), and [L4\\_IPC\\_NEVER](#).

Here is the call graph for this function:

**15.185.2.2 up()**

```

l4_msgtag_t L4::Semaphore::up (
    l4_utcb_t * utcb = l4_utcb()) [inline], [noexcept]
  
```

[Semaphore](#) up operation (wrapper for [trigger\(\)](#)).

**Parameters**

<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. See <a href="#">l4_utcb</a> .
-------------	--

**Returns**


Syscall return tag for a send-only operation, this means there is no return value except [L4\\_MSGTAG\\_ERROR](#) indicating success or failure of the send operation. Use [l4\\_ipc\\_error\(\)](#) to check for errors and **do not** use [l4\\_error\(\)](#).

Increases the semaphore counter by one if it is smaller than an unspecified limit. The unspecified limit is guaranteed to be at least  $2^{31}-1$ .

Definition at line 67 of file [semaphore](#).

References [L4::Triggerable::trigger\(\)](#).

Here is the call graph for this function:



The documentation for this struct was generated from the following file:


- [l4/sys/semaphore](#)

## 15.186 L4::Server< LOOP\_HOOKS > Class Template Reference


Basic server loop for handling client requests.

```
#include <ipc_server_loop>
```

Inheritance diagram for L4::Server< LOOP\_HOOKS >:



Collaboration diagram for L4::Server< LOOP\_HOOKS >:



## Public Member Functions

- `Server (l4_utcb_t *)`  
*Initializes the server loop.*
- `Server ()`  
*Initializes the server loop.*
- `template<typename DISPATCH>`  
`L4_NORETURN void internal_loop (DISPATCH dispatch, l4_utcb_t *)`  
*The server loop.*
- `template<typename R>`  
`L4_NORETURN void loop_noexc (R r, l4_utcb_t *u=l4_utcb())`  
*Server loop without exception handling.*
- `template<typename EXC, typename R>`  
`L4_NORETURN void loop (R r, l4_utcb_t *u=l4_utcb())`

*Server loop with internal exception handling.*

- template<typename EXC, typename R, typename Printer>  
L4::NORETURN void loop\_dbg (R r, Printer p, l4\_utcb\_t \*u=l4\_utcb())  
*Server loop with internal exception handling including message printing.*

## Public Member Functions inherited from L4::lpc\_svr::Br\_manager\_no\_buffers

- int alloc\_buffer\_demand (Demand const &demand) override  
*Tells the server to allocate buffers for the given demand.*
- L4::Cap< void > get\_rcv\_cap (int) const override  
*Returns L4::Cap<void>::Invalid, we have no buffer management.*
- int realloc\_rcv\_cap (int) override  
*Returns -L4\_ENOMEM, we have no buffer management.*
- int add\_timeout (Timeout \*, l4\_kernel\_clock\_t) override  
*Returns -L4\_ENOSYS, we have no timeout queue.*
- int remove\_timeout (Timeout \*) override  
*Returns -L4\_ENOSYS, we have no timeout queue.*

## Public Member Functions inherited from L4::lpc\_svr::Server\_iface

- Server\_iface ()  
*Make a server interface.*
- template<typename T>  
L4::Cap< T > rcv\_cap (int index) const  
*Get given receive buffer as typed capability.*
- L4::Cap< void > rcv\_cap (int index) const  
*Get receive cap with the given index as generic (void) type.*

## Protected Member Functions

- l4\_msgtag\_t reply\_n\_wait (l4\_msgtag\_t reply, l4\_umword\_t \*p, l4\_utcb\_t \*)  
*Internal implementation for reply and wait.*

## Protected Member Functions inherited from L4::lpc\_svr::Br\_manager\_no\_buffers

- unsigned first\_free\_br () const  
*Returns 1 as first free buffer.*
- void setup\_wait (l4\_utcb\_t \*utcb, L4::lpc\_svr::Reply\_mode)  
*Setup wait function for the server loop (Server<>).*

## Additional Inherited Members

## Public Types inherited from L4::lpc\_svr::Server\_iface

- typedef L4::Type\_info::Demand Demand  
*Data type expressing server-side demand for receive buffers.*

### 15.186.1 Detailed Description

```
template<typename LOOP_HOOKS = ipc_svr::Default_loop_hooks>
class L4::Server< LOOP_HOOKS >
```

Basic server loop for handling client requests.

#### Parameters

<i>LOOP_HOOKS</i>	the server inherits from LOOP_HOOKS and calls the hooks defined in LOOP_HOOKS in the server loop. See <a href="#">ipc_svr::Default_loop_hooks</a> , <a href="#">ipc_svr::Ignore_errors</a> , <a href="#">ipc_svr::Default_timeout</a> , <a href="#">ipc_svr::Compound_reply</a> , and <a href="#">ipc_svr::Br_manager_no_buffers</a> .
-------------------	--

This is basically a simple server loop that uses a single message buffer for receiving requests and sending replies. The dispatcher determines how incoming messages are handled.

Definition at line 307 of file [ipc\\_server\\_loop](#).

### 15.186.2 Constructor & Destructor Documentation

#### 15.186.2.1 Server()

```
template<typename LOOP_HOOKS = Ipc_svr::Default_loop_hooks>
L4::Server< LOOP_HOOKS >::Server (
    l4_utcb_t * ) [inline], [explicit]
```

Initializes the server loop.

Note that this variant is deprecated. The UTCB can be specified with the server loop function ([l4\\_utcb\(\)](#) is the default). (2021-10)

Definition at line 319 of file [ipc\\_server\\_loop](#).

### 15.186.3 Member Function Documentation

#### 15.186.3.1 internal\_loop()

```
template<typename L>
template<typename DISPATCH>
L4_NORETURN void L4::Server< L >::internal_loop (
    DISPATCH dispatch,
    l4_utcb_t * utcb) [inline]
```

The server loop.

This function usually never returns, it waits for incoming messages calls the dispatcher, sends a reply and waits again.


Definition at line 405 of file [ipc\\_server\\_loop](#).

References [l4\\_msgtag\\_t::has\\_error\(\)](#), [L4\\_ENOREPLY](#), [l4\\_msgtag\(\)](#), and [reply\\_n\\_wait\(\)](#).




Referenced by [loop\(\)](#), [loop\\_dbg\(\)](#), and [loop\\_noexc\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 15.186.3.2 loop()

```

template<typename LOOP_HOOKS = Ipc_svr::Default_loop_hooks>
template<typename EXC, typename R>
L4_NORETURN void L4::Server< LOOP_HOOKS >::loop (
    R r,
    l4_utcb_t * u = l4_utcb()) [inline]
  
```

[Server](#) loop with internal exception handling.

This server loop translates [L4::Runtime\\_error](#) exceptions into negative error return codes sent to the caller.

Definition at line 355 of file [ipc\\_server\\_loop](#).

### 15.186.3.3 loop\_dbg()

```
template<typename LOOP_HOOKS = Ipc_svr::Default_loop_hooks>
template<typename EXC, typename R, typename Printer>
L4_NORETURN void L4::Server< LOOP_HOOKS >::loop_dbg (
    R r,
    Printer p,
    l4_utcb_t * u = l4_utcb()) [inline]
```

Server loop with internal exception handling including message printing.

Exceptions are translated into error codes, just like in [loop\(\)](#). In addition, error messages are printed using the Printer argument.

Definition at line 368 of file [ipc\\_server\\_loop](#).

The documentation for this class was generated from the following file:


- [l4/sys/cxx/ipc\\_server\\_loop](#)

## 15.187 L4::Server\_object Class Reference


Abstract server object to be used with [L4::Server](#) and [L4::Basic\\_registry](#).

```
#include <ipc_server>
```

Inheritance diagram for L4::Server\_object:



Collaboration diagram for L4::Server\_object:



### Public Member Functions

- virtual int `dispatch` (unsigned long rights, `lpc::lostream` &ios)=0  
*The abstract handler for client requests to the object.*
- `l4_msgtag_t` `dispatch` (`l4_msgtag_t` tag, unsigned rights, `l4_utcb_t` \*utcb) override  
*The abstract handler for client requests to the object.*

### Public Member Functions inherited from `L4::Epiface`

- **Epiface** ()  
*Make a server object.*
- virtual `Demand` `get_buffer_demand` () const =0  
*Get the server-side receive buffer demand for this object.*
- virtual `~Epiface` ()=0  
*Destroy the object.*
- Stored\_cap `obj_cap` () const  
*Get the capability to the kernel object belonging to this object.*
- `Server_iface` \* `server_iface` () const  
*Get pointer to server interface at which the object is currently registered.*
- int `set_server` (`Server_iface` \*srv, `Cap`< void > cap, bool managed=false)  
*Set server registration info for the object.*
- void **set\_obj\_cap** (`Cap`< void > const &cap)  
*Deprecated server registration function.*

## Additional Inherited Members

## Public Types inherited from L4::Epiface

- typedef [lpc\\_svr::Server\\_iface](#) **Server\_iface**  
*Type for abstract server interface.*
- typedef [lpc\\_svr::Server\\_iface::Demand](#) **Demand**  
*Type for server-side receive buffer demand.*

## 15.187.1 Detailed Description

Abstract server object to be used with [L4::Server](#) and [L4::Basic\\_registry](#).

### Note

Usually [L4::Server\\_object\\_t](#) is used as a base class when writing server objects.

This server object provides an abstract interface that is used by the [L4::Registry\\_dispatcher](#) model. You can derive subclasses from this interface and implement application specific server objects.

Definition at line 38 of file [ipc\\_server](#).

## 15.187.2 Member Function Documentation

### 15.187.2.1 dispatch() [1/2]

```
l4_msgtag_t L4::Server_object::dispatch (
    l4_msgtag_t tag,
    unsigned rights,
    l4_utcb_t * utcb) [inline], [override], [virtual]
```

The abstract handler for client requests to the object.

### Parameters

<i>tag</i>	The message tag for this invocation.
<i>rights</i>	The rights bits in the invoked capability.
<i>utcb</i>	The UTCB used for the invocation.

### Return values

<code>-L4_ENOREPLY</code>	No reply message is send.
<code>&lt;0</code>	Error, reply with error code.
<code>&gt;=0</code>	Success, reply with return value.


This function must be implemented by application specific server objects.

Implements [L4::Epiface](#).

Definition at line 60 of file [ipc\\_server](#).

References [dispatch\(\)](#).

Here is the call graph for this function:



### 15.187.2.2 `dispatch()` [2/2]

```
virtual int L4::Server_object::dispatch (
    unsigned long rights,
    Ipc::Iostream & ios) [pure virtual]
```

The abstract handler for client requests to the object.

#### Parameters

<i>rights</i>	The rights bits in the invoked capability.
<i>ios</i>	The <a href="#">Ipc::Iostream</a> for reading the request and writing the reply.

#### Return values

<code>-L4_ENOREPLY</code>	Instructs the server loop to not send a reply.
<code>&lt; 0</code>	Error, reply with error code.
<code>&gt;= 0</code>	Success, reply with return value.

This function must be implemented by application specific server objects. The implementation must unmarshall data from the stream (`ios`) and create a reply by marshalling to the stream (`ios`). For details about the IPC stream see [IPC stream operators](#).

#### Note

You need to extract the complete message from the `ios` stream before inserting any reply data or before doing any function call that may use the UTCB. Otherwise, the incoming message may get lost.


Implemented in [L4::Server\\_object\\_x< Derived, IFACE, BASE >](#).

#### Examples

[examples/libs/l4re/c++/shared\\_ds/ds\\_srv.cc](#), and [examples/libs/l4re/streammap/server.cc](#).

Referenced by [dispatch\(\)](#).

Here is the caller graph for this function:



The documentation for this class was generated from the following file:


- [l4/cxx/ipc\\_server](#)

## 15.188 L4::Server\_object\_t< IFACE, BASE > Struct Template Reference

Base class (template) for server implementing server objects.


```
#include <ipc_server>
```

Inheritance diagram for L4::Server\_object\_t< IFACE, BASE >:





Collaboration diagram for L4::Server\_object\_t< IFACE, BASE >:



## Public Types

- typedef **IFACE Interface**  
*Data type of the IPC interface definition.*

## Public Types inherited from **L4::Epiface**

- typedef **lpc\_svr::Server\_iface Server\_iface**  
*Type for abstract server interface.*
- typedef **lpc\_svr::Server\_iface::Demand Demand**  
*Type for server-side receive buffer demand.*

## Public Member Functions

- `BASE::Demand` [get\\_buffer\\_demand](#) () const override
- int [dispatch\\_meta\\_request](#) ([L4::lpc::lostream](#) &ios)

*Implementation of the meta protocol based on IFACE.*

## Public Member Functions inherited from [L4::Server\\_object](#)

- virtual int [dispatch](#) (unsigned long rights, [lpc::lostream](#) &ios)=0  
*The abstract handler for client requests to the object.*
- [l4\\_msgtag\\_t](#) [dispatch](#) ([l4\\_msgtag\\_t](#) tag, unsigned rights, [l4\\_utcb\\_t](#) \*utcb) override  
*The abstract handler for client requests to the object.*

## Public Member Functions inherited from [L4::Epiface](#)

- **Epiface** ()  
*Make a server object.*
- virtual ~**Epiface** ()=0  
*Destroy the object.*
- Stored\_cap [obj\\_cap](#) () const  
*Get the capability to the kernel object belonging to this object.*
- [Server\\_iface](#) \* [server\\_iface](#) () const  
*Get pointer to server interface at which the object is currently registered.*
- int [set\\_server](#) ([Server\\_iface](#) \*srv, [Cap](#)< void > cap, bool managed=false)  
*Set server registration info for the object.*
- void [set\\_obj\\_cap](#) ([Cap](#)< void > const &cap)  
*Deprecated server registration function.*

## Static Public Member Functions

- template<typename THIS>  
static int [proto\\_dispatch](#) (THIS \*self, [l4\\_umword\\_t](#) rights, [L4::lpc::lostream](#) &ios)  
*Implementation of protocol-based dispatch for this server object.*

## 15.188.1 Detailed Description

```
template<typename IFACE, typename BASE = L4::Server_object>
struct L4::Server_object_t< IFACE, BASE >
```

Base class (template) for server implementing server objects.

### Template Parameters

<i>IFACE</i>	The IPC interface class that defines the interface that shall be implemented.
<i>BASE</i>	The server object base class (usually <a href="#">L4::Server_object</a> ).

### Examples

[examples/libs/l4re/c++/shared\\_ds/ds\\_srv.cc](#), and [examples/libs/l4re/streammap/server.cc](#).

Definition at line 80 of file [ipc\\_server](#).

## 15.188.2 Member Function Documentation

### 15.188.2.1 dispatch\_meta\_request()

```
template<typename IFACE, typename BASE = L4::Server_object>
int L4::Server_object_t< IFACE, BASE >::dispatch_meta_request (
    L4::Ipc::Iostream & ios) [inline]
```

Implementation of the meta protocol based on *IFACE*.

#### Parameters

<i>ios</i>	The IO stream used for receiving the message.
------------	---

This function can be used to handle incoming [L4\\_PROTO\\_META](#) protocol requests. The implementation uses the [L4::Type\\_info](#) of *IFACE* to handle the requests. Call this function in the implementation of [Server\\_object::dispatch\(\)](#) when the received message tag has protocol [L4\\_PROTO\\_META](#) ([L4::Meta::Protocol](#)).

Definition at line 99 of file [ipc\\_server](#).

### 15.188.2.2 get\_buffer\_demand()

```
template<typename IFACE, typename BASE = L4::Server_object>
BASE::Demand L4::Server_object_t< IFACE, BASE >::get_buffer_demand () const [inline], [override],
[virtual]
```

#### Returns

the server-side buffer demand based in *IFACE*.

Implements [L4::Epiface](#).

Definition at line 86 of file [ipc\\_server](#).

### 15.188.2.3 proto\_dispatch()

```
template<typename IFACE, typename BASE = L4::Server_object>
template<typename THIS>
int L4::Server_object_t< IFACE, BASE >::proto_dispatch (
    THIS * self,
    l4_umword_t rights,
    L4::Ipc::Iostream & ios) [inline], [static]
```

Implementation of protocol-based dispatch for this server object.

#### Parameters

<i>self</i>	The this pointer for the object (inherits from <a href="#">Server_object_t</a> ).
-------------	---

<i>rights</i>	The rights from the received IPC (forwarded to <code>p_dispatch()</code> ).
<i>ios</i>	The message stream for the incoming and the reply message.


Server objects may call this function from their `dispatch()` function. This function reads the protocol ID from the message tag and uses the `p_dispatch` code to dispatch to overloaded `p_dispatch` functions of self.

Definition at line 114 of file `ipc_server`.


References `l4_msgtag_t::label()`, and `L4::Kobject_typeid< T >::proto_dispatch()`.

Referenced by `L4::Server_object_x< Derived, IFACE, BASE >::dispatch()`.

Here is the call graph for this function:



Here is the caller graph for this function:



The documentation for this struct was generated from the following file:


- `l4/cxx/ipc_server`

## 15.189 L4::Server\_object\_x< Derived, IFACE, BASE > Struct Template Reference


Helper class to implement `p_dispatch` based server objects.

```
#include <ipc_server>
```

Inheritance diagram for L4::Server\_object\_x< Derived, IFACE, BASE >:



Collaboration diagram for L4::Server\_object\_x< Derived, IFACE, BASE >:



## Public Member Functions

- `int dispatch (l4_umword_t r, L4::lpc::lostream &ios)`  
Implementation forwarding to `p_dispatch()`.

## Public Member Functions inherited from L4::Server\_object

- `l4_msgtag_t dispatch (l4_msgtag_t tag, unsigned rights, l4_utcb_t *utcb)` override

*The abstract handler for client requests to the object.*

## Public Member Functions inherited from L4::Epiface

- **Epiface** ()  
*Make a server object.*
- virtual ~**Epiface** ()=0  
*Destroy the object.*
- Stored\_cap **obj\_cap** () const  
*Get the capability to the kernel object belonging to this object.*
- **Server\_iface** \* **server\_iface** () const  
*Get pointer to server interface at which the object is currently registered.*
- int **set\_server** (**Server\_iface** \*srv, **Cap**< void > cap, bool managed=false)  
*Set server registration info for the object.*
- void **set\_obj\_cap** (**Cap**< void > const &cap)  
*Deprecated server registration function.*

## Public Member Functions inherited from L4::Server\_object\_t< IFACE, L4::Server\_object >

- L4::Server\_object::Demand **get\_buffer\_demand** () const override
- int **dispatch\_meta\_request** (L4::lpc::lostream &ios)  
*Implementation of the meta protocol based on IFACE.*

## Additional Inherited Members

## Public Types inherited from L4::Epiface

- typedef **lpc\_svr::Server\_iface** **Server\_iface**  
*Type for abstract server interface.*
- typedef **lpc\_svr::Server\_iface::Demand** **Demand**  
*Type for server-side receive buffer demand.*

## Public Types inherited from L4::Server\_object\_t< IFACE, L4::Server\_object >

- typedef IFACE **Interface**  
*Data type of the IPC interface definition.*

## Static Public Member Functions inherited from L4::Server\_object\_t< IFACE, L4::Server\_object >

- static int **proto\_dispatch** (THIS \*self, **l4\_umword\_t** rights, L4::lpc::lostream &ios)  
*Implementation of protocol-based dispatch for this server object.*

### 15.189.1 Detailed Description

```
template<typename Derived, typename IFACE, typename BASE = L4::Server_object>
struct L4::Server_object_x< Derived, IFACE, BASE >
```

Helper class to implement p\_dispatch based server objects.

#### Template Parameters

<i>Derived</i>	The data type of your server object class.
<i>IFACE</i>	The data type providing the interface definition for the object.
<i>BASE</i>	Optional data-type of the base server object (usually <a href="#">L4::Server_object</a> )

This class implements the standard [dispatch\(\)](#) function of [L4::Server\\_object](#) and forwards incoming messages to a set of overloaded p\_dispatch() functions. There must be a p\_dispatch() function in Derived for each interface provided by IFACE with the signature

```
int p_dispatch(Iface *, unsigned rights, L4::Ipc::Iostream &)
```

that is called for messages with protocol == Iface::Protocol.

Example signature for [L4Re::Dataspace](#) is:

```
int p_dispatch(L4Re::Dataspace *, unsigned, L4::Ipc::Iostream &)
```

Definition at line [143](#) of file [ipc\\_server](#).

The documentation for this struct was generated from the following file:

- [l4/cxx/ipc\\_server](#)


## 15.190 L4::Smart\_cap< T, SMART > Class Template Reference

Smart capability class.


```
#include <smart_capability>
```



Inheritance diagram for L4::Smart\_cap< T, SMART >:



Collaboration diagram for L4::Smart\_cap< T, SMART >:



### Public Member Functions

- `template<typename O>`  
`Smart_cap (Cap< O > const &p) noexcept`  
*Internal constructor, use to generate a capability from a `this` pointer.*
- `Cap< T > operator-> ( ) const noexcept`  
*Member access of a `T`.*

### Public Member Functions inherited from **L4::Cap\_base**

- `l4_cap_idx_t cap ( ) const noexcept`

- Return capability selector.*

  - `bool is_valid ()` const noexcept  
*Test whether the capability is a valid capability index (i.e., not L4\_INVALID\_CAP).*
  - `int invalid_cap_error ()` const noexcept  
*Return the transported error code in an invalid capability index.*
  - `l4_fpage_t fpage` (unsigned rights=L4\_CAP\_FPAGE\_RWS) const noexcept  
*Return flexpage for the capability.*
  - `l4_umword_t snd_base` (unsigned grant=L4\_MAP\_ITEM\_MAP, l4\_cap\_idx\_t base=L4\_INVALID\_CAP) const noexcept  
*Return send base.*
  - `bool operator== (Cap_base const &o)` const noexcept  
*Test if two capabilities are equal.*
  - `bool operator!= (Cap_base const &o)` const noexcept  
*Test if two capabilities are not equal.*
  - `l4_msgtag_t validate (l4_utcb_t *u=l4_utcb())` const noexcept  
*Check whether a capability is present (refers to an object).*
  - `l4_msgtag_t validate (Cap< Task > task, l4_utcb_t *u=l4_utcb())` const noexcept  
*Check whether a capability is present (refers to an object).*
  - `void invalidate ()` noexcept  
*Set this capability to invalid (L4\_INVALID\_CAP).*

### Additional Inherited Members

### Public Types inherited from L4::Cap\_base

- enum `No_init_type` { `No_init` }  
*Special value for uninitialized capability objects.*
- enum `Cap_type` { `Invalid` = L4\_INVALID\_CAP }  
*Invalid capability type.*

### Protected Member Functions inherited from L4::Cap\_base

- `Cap_base (l4_cap_idx_t c)` noexcept  
*Generate a capability from its C representation.*
- `Cap_base (Cap_type cap)` noexcept  
*Constructor to create an invalid capability.*
- `Cap_base (l4_default_caps_t cap)` noexcept  
*Initialize capability with one of the default capabilities.*
- `Cap_base ()` noexcept  
*Create an uninitialized instance.*
- `void move (Cap_base const &src)` const  
*Replace this capability with the contents of src.*
- `void copy (Cap_base const &src)` const  
*Copy a capability.*

### Protected Attributes inherited from L4::Cap\_base

- `l4_cap_idx_t _c`  
*The C representation of a capability selector.*

### 15.190.1 Detailed Description

```
template<typename T, typename SMART>
class L4::Smart_cap< T, SMART >
```

Smart capability class.

Definition at line 25 of file [smart\\_capability](#).

### 15.190.2 Constructor & Destructor Documentation

#### 15.190.2.1 Smart\_cap()

```
template<typename T, typename SMART>
template<typename O>
L4::Smart_cap< T, SMART >::Smart_cap (
    Cap< O > const & p) [inline], [noexcept]
```

Internal constructor, use to generate a capability from a `this` pointer.

#### Attention

This constructor is only useful to generate a capability from the `this` pointer of an objected that is an [L4::Kobject](#). Do *never* use this constructor for something else!

#### Parameters

<i>p</i>	The <code>this</code> pointer of the <a href="#">Kobject</a> or derived object
----------	--

Definition at line 62 of file [smart\\_capability](#).

The documentation for this class was generated from the following file:


- [I4/sys/smart\\_capability](#)

## 15.191 L4::String Class Reference

A null-terminated string container class.

```
#include <string.h>
```

Collaboration diagram for L4::String:



### 15.191.1 Detailed Description

A null-terminated string container class.

Definition at line 22 of file [string.h](#).

The documentation for this class was generated from the following file:


- l4/cxx/[string.h](#)

## 15.192 L4::Task Class Reference


C++ interface of the [Task](#) kernel object, see [Task](#) for the C interface.

```
#include <task>
```

Inheritance diagram for L4::Task:



Collaboration diagram for L4::Task:



## Public Member Functions

- `l4_msgtag_t map (Cap< Task > const &src_task, l4_fpage_t const &snd_fpage, l4_umword_t snd_base, l4_utcb_t *utcb=l4_utcb()) noexcept`  
*Map resources available in the source task to a destination task.*
- `l4_msgtag_t unmap (l4_fpage_t const &fpag, l4_umword_t map_mask, l4_utcb_t *utcb=l4_utcb()) noexcept`  
*Revoke rights from the task.*

- `l4_msgtag_t unmap_batch` (`l4_fpage_t` const \*fpages, unsigned num\_fpages, `l4_umword_t` map\_mask, `l4_utcb_t` \*utcb=`l4_utcb()`) noexcept  
*Revoke rights from a task.*
- `l4_msgtag_t delete_obj` (`L4::Cap`< void > obj, `l4_utcb_t` \*utcb=`l4_utcb()`) noexcept  
*Release capability and delete object.*
- `l4_msgtag_t release_cap` (`L4::Cap`< void > cap, `l4_utcb_t` \*utcb=`l4_utcb()`) noexcept  
*Release object capability.*
- `l4_msgtag_t cap_valid` (`Cap`< void > const &cap, `l4_utcb_t` \*utcb=`l4_utcb()`) noexcept  
*Check whether a capability is present (refers to an object).*
- `l4_msgtag_t cap_equal` (`Cap`< void > const &cap\_a, `Cap`< void > const &cap\_b, `l4_utcb_t` \*utcb=`l4_utcb()`) noexcept  
*Test whether two capabilities point to the same object with the same permissions (only considering selected permissions).*
- `l4_msgtag_t add_ku_mem` (`l4_fpage_t` \*fpage, `l4_utcb_t` \*utcb=`l4_utcb()`) noexcept  
*Add kernel-user memory.*

## Public Member Functions inherited from `L4::Kobject`

- `l4_msgtag_t dec_refcnt` (`l4_mword_t` diff, `l4_utcb_t` \*utcb=`l4_utcb()`)  
*Decrement the in kernel reference counter for the object.*

## Additional Inherited Members

## Protected Types inherited from

`L4::Kobject_t`< `Task`, `Kobject`, `L4_PROTO_TASK`, `Type_info::Demand_t`< 2 > >

- typedef `Task` **Class**  
*The target interface type (inheriting from `Kobject_t`).*
- typedef `Typeid::Iface`< `PROTO`, `Task` > **\_\_Iface**  
*The interface description for the derived class.*
- typedef `Typeid::Merge_list`< `Typeid::Iface_list`< **\_\_Iface** >, typename `Kobject::__Iface_list` > **\_\_Iface\_list**  
*The list of all RPC interfaces provided directly or through inheritance.*

## Protected Member Functions inherited from

`L4::Kobject_t`< `Task`, `Kobject`, `L4_PROTO_TASK`, `Type_info::Demand_t`< 2 > >

- `L4::Cap`< `Class` > **c** () const noexcept  
*Get the capability to ourselves.*

## Protected Member Functions inherited from `L4::Kobject`

- `l4_cap_idx_t cap` () const noexcept  
*Return capability selector.*

## Static Protected Member Functions inherited from

`L4::Kobject_t`< `Task`, `Kobject`, `L4_PROTO_TASK`, `Type_info::Demand_t`< 2 > >

- static void **\_\_check\_protocols** () noexcept  
*Helper to check for protocol conflicts.*



## 15.192.1 Detailed Description

C++ interface of the [Task](#) kernel object, see [Task](#) for the C interface.

The [L4::Task](#) class represents a combination of the address spaces provided by the [L4Re](#) micro kernel. A task consists of at least a memory address space and an object address space. On IA32 there is also an IO-port address space associated with an [L4::Task](#).

[L4::Task](#) objects are created using the [L4::Factory](#) interface.

### Include File

```
#include <l4/sys/task>
```

Definition at line 33 of file [task](#).

## 15.192.2 Member Function Documentation

### 15.192.2.1 add\_ku\_mem()

```
l4_msgtag_t L4::Task::add_ku_mem (
    l4_fpage_t * fpage,
    l4_utcb_t * utcb = l4_utcb()) [inline], [noexcept]
```

Add kernel-user memory.

#### Parameters

<i>in, out</i>	<i>fpage</i>	Flexpage describing the virtual area the memory goes to. On systems without MMU, the flexpage is adjusted to reflect the actually allocated physical address.
	<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. Defaults to <a href="#">l4_utcb</a> .

#### Returns

Syscall return tag

Kernel-user memory (ku\_mem) is memory that is shared between the kernel and user-space. It is needed for the UTCB area of threads (see [L4::Thread::Attr::bind\(\)](#)) and for (extended) vCPU state. Note that existing kernel-user memory cannot be unmapped or mapped somewhere else.

## Note

The amount of kernel-user memory that can be allocated at once is limited by the used kernel implementation. The minimum allocatable amount is one page ([L4\\_PAGESIZE](#)). A portable implementation should not depend on allocations greater than 16KiB to succeed.

This function is only guaranteed to work on [L4::Task](#) objects. It might or might not work on [L4::Vm](#) objects or on [L4Re::Dma\\_space](#) objects but there is no practical use for adding kernel-user memory to [L4::Vm](#) objects or to [L4Re::Dma\\_space](#) objects.

Definition at line 281 of file [task](#).

References [L4::Kobject::cap\(\)](#).

Here is the call graph for this function:



### 15.192.2.2 cap\_equal()

```

l4_msgtag_t L4::Task::cap_equal (
    Cap< void > const & cap_a,
    Cap< void > const & cap_b,
    l4_utcb_t * utcb = l4_utcb()) [inline], [noexcept]
  
```

Test whether two capabilities point to the same object with the same permissions (only considering selected permissions).

#### Parameters

<i>cap<sub>a</sub></i>	Capability selector for the first capability to compare.
<i>cap<sub>b</sub></i>	Capability selector for the second capability to compare.
<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. Defaults to <a href="#">l4_utcb</a> .

#### Return values

<i>l4_msgtag_t::label()</i> = 1	The compared capabilities point to the same object with same considered permission.
<i>l4_msgtag_t::label()</i> = 0	The compared capabilities do <b>not</b> point to the same object or differ in the considered permission.

- For [L4::lpc\\_gate](#) objects, only the permissions [L4\\_CAP\\_FPAGE\\_W](#), [L4\\_CAP\\_FPAGE\\_S](#), and [L4\\_FPAGE\\_C\\_OBJ\\_RIGHT1](#) are considered for the comparison. Differences in other permissions are ignored.


- For other objects, only the permissions [L4\\_CAP\\_FPAGE\\_W](#) and [L4\\_CAP\\_FPAGE\\_S](#) are considered for the comparison. Differences in other permissions are ignored.

Note that having the [L4\\_CAP\\_FPAGE\\_R](#) permission is implicit in possessing the capability.

Definition at line 251 of file [task](#).

References [L4::Cap\\_base::cap\(\)](#), and [L4::Kobject::cap\(\)](#).

Here is the call graph for this function:



### 15.192.2.3 cap\_valid()

```

l4_msgtag_t L4::Task::cap_valid (
    Cap< void > const & cap,
    l4_utcb_t * utcb = l4_utcb()) [inline], [noexcept]
  
```

Check whether a capability is present (refers to an object).

#### Parameters

<i>cap</i>	Valid capability to check for presence.
<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. Defaults to <a href="#">l4_utcb</a> .

#### Return values

<i>l4_msgtag_t::label()</i> > 0	Capability is present (refers to an object).
<i>l4_msgtag_t::label()</i> == 0	No capability present (void object).

A capability is considered present when it refers to an existing kernel object.


**Precondition**

`cap` must be a valid capability (i.e. `cap.is_valid() == true`). If you are unsure about the validity of your capability use [L4::Cap.validate\(\)](#) instead.

Definition at line 222 of file [task](#).

References [L4::Cap\\_base::cap\(\)](#), and [L4::Kobject::cap\(\)](#).

Here is the call graph for this function:

**15.192.2.4 delete\_obj()**

```

l4_msgtag_t L4::Task::delete_obj (
    L4::Cap< void > obj,
    l4_utcb_t * utcb = l4_utcb()) [inline], [noexcept]
  
```

Release capability and delete object.

**Parameters**

<i>obj</i>	Capability index of the object to delete.
<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. Defaults to <a href="#">l4_utcb</a> .

**Returns**

Syscall return tag

If `obj` has the delete permission, initiates the deletion of the object. This implies that all capabilities for that object are gone afterwards. However, kernel-internally, objects are not destroyed until all other kernel objects holding a reference to it drop the reference. Hence, quota used by that object might not be freed immediately.


If `obj` does not have the delete permission, no error will be reported and only the capability `obj` is removed. (Note that, depending on the object's reference counter, this might still imply initiation of deletion.)

This operation is equivalent to [unmap\(\)](#) with [L4\\_FP\\_DELETE\\_OBJ](#) flag.

Definition at line 180 of file [task](#).

References [L4::Cap\\_base::cap\(\)](#), and [L4::Kobject::cap\(\)](#).

Here is the call graph for this function:



### 15.192.2.5 map()

```

l4_msgtag_t L4::Task::map (
    Cap< Task > const & src_task,
    l4_fpage_t const & snd_fpage,
    l4_umword_t snd_base,
    l4_utcb_t * utcb = l4_utcb()) [inline], [noexcept]
  
```

Map resources available in the source task to a destination task.

#### Parameters

<i>src_task</i>	Capability selector of the source task.
<i>snd_fpage</i>	Send flexpage that describes an area in the address space or object space of the source task.
<i>snd_base</i>	Send base that describes an offset in the receive window of the destination task. The lower bits contain additional map control flags (see <a href="#">l4_fpage_cacheability_opt_t</a> for memory mappings, <a href="#">Attributes and additional permissions for object send items</a> for object mappings, and <a href="#">L4_MAP_ITEM_GRANT</a> ; also see <a href="#">l4_map_control()</a> and <a href="#">l4_map_obj_control()</a> ).
<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. Defaults to <a href="#">l4_utcb</a> .

#### Returns

Syscall return tag. The function [l4\\_error\(\)](#) shall be used to test if the map operation was successful.

#### Return values

<code>L4_EOK</code>	Operation successful (but see notes below).
<code>-L4_EPERM</code>	Insufficient permissions; see precondition.
<code>-L4_EINVAL</code>	Invalid source task capability.
<code>-L4_IPC_SEMAPFAILED</code>	The map operation failed due to limited quota.

**Precondition**

The invoked [Task](#) capability must have the permission [L4\\_CAP\\_FPAGE\\_W](#).

This method allows for asynchronous transfer of capabilities, memory mappings, and IO-port mappings (on IA32) from one task to another. The destination task is the task referenced by the capability on which the map is invoked, and the receive window is the whole address space of that task. By specifying proper rights in the `snd_fpage` and `snd_base`, it is possible to remove rights during transfer.

**Note**

If the send flexpage is of type [L4\\_FPAGE\\_OBJ](#), the [L4\\_CAP\\_FPAGE\\_S](#) right is removed from the transferred capability unless both the source and destination task capabilities possess the [L4\\_CAP\\_FPAGE\\_S](#) right themselves.

Even with [l4\\_error\(\)](#) returning `L4_EOK` there might be cases where not all pages of the send flexpage were mapped respectively granted to the destination task, for instance, if the corresponding mapping in the destination task does already exist.

For more information on spaces and mappings, see [Spaces and Mappings](#). The flexpage API is described in more detail at [Flexpages](#).


**Note**

For peculiarities when using grant, see [L4\\_MAP\\_ITEM\\_GRANT](#).

Definition at line 85 of file [task](#).

References [L4::Cap\\_base::cap\(\)](#), and [L4::Kobject::cap\(\)](#).

Here is the call graph for this function:

**15.192.2.6 release\_cap()**

```

l4_msgtag_t L4::Task::release_cap (
    L4::Cap< void > cap,
    l4_utcb_t * utcb = l4_utcb()) [inline], [noexcept]
  
```

Release object capability.

**Parameters**

<i>cap</i>	Capability selector of the object to release.
<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. Defaults to <a href="#">l4_utcb</a> .

**Returns**

Syscall return tag.

This operation unmaps the capability from `this` task. This operation is equivalent to unmapping a single object capability by specifying all object rights as unmap mask.


**Note**

If the reference counter of the kernel object referenced by [cap](#) goes down to zero, the deletion of the object is initiated. Objects are not destroyed until all other kernel objects holding a reference to it drop the reference.

Definition at line 201 of file [task](#).

References [L4::Cap\\_base::cap\(\)](#), and [L4::Kobject::cap\(\)](#).

Here is the call graph for this function:

**15.192.2.7 unmap()**

```

l4_msgtag_t L4::Task::unmap (
    l4_fpage_t const & fpage,
    l4_unword_t map_mask,
    l4_utcb_t * utcb = l4_utcb()) [inline], [noexcept]
  
```

Revoke rights from the task.

**Parameters**

<i>fpage</i>	Flexpage that describes an area in one capability space of <code>this</code> task and the rights to revoke.
<i>map_mask</i>	Unmap mask, see <a href="#">l4_unmap_flags_t</a>

<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. Defaults to <a href="#">l4_utcb</a> .
-------------	--

## Returns

Syscall return tag

This method allows to revoke rights from the destination task. The rights to revoke are specified in the flexpage, see [l4\\_fpage\\_rights\(\)](#). For a flexpage describing IO ports or memory, it also revokes rights from all the tasks that got the rights delegated from the destination task (i.e., this operation does a recursive rights revocation). The capability is unmapped if certain rights are specified, see below for details. It is guaranteed that the rights revocation is completed before this function returns.

Note that this function cannot be used to revoke the reference counting permission (see [L4\\_FPAGE\\_C\\_REF\\_CNT](#)) or the IPC-gate server permission (see [L4\\_FPAGE\\_C\\_IPCGATE\\_SVR](#)) from object capabilities.

It depends on the platform and the object type which rights need to be specified in the `rights` field of `fpage` to unmap a capability:

- An object capability is unmapped if and only if the [L4\\_CAP\\_FPAGE\\_R](#) right bit is set.
- An IO port is unmapped if and only if any right bit is set.
- Memory is unmapped if and only if the [L4\\_FPAGE\\_RO](#) right bit is set.

## Note

Depending on the page-table features supported by the hardware, revocation of certain rights from a memory capability can be a no-op (i.e., the rights are not revoked). Further, revocation of certain rights may grant other rights which were not present before. For instance, on an architecture without support for NX, revoking X does nothing. For another example, revoking only X from an execute-only page grants read permission (because the mapping remains present in the page table).

If the reference counter of a kernel object referenced in `fpage` goes down to zero (as a result of deleting capabilities), the deletion of the object is initiated. Objects are not destroyed until all other kernel objects holding a reference to it drop the reference.

Definition at line [135](#) of file [task](#).

References [L4::Kobject::cap\(\)](#).

Here is the call graph for this function:





### 15.192.2.8 unmap\_batch()

```
l4_msgtag_t L4::Task::unmap_batch (
    l4_fpage_t const * fpages,
    unsigned num_fpages,
    l4_umword_t map_mask,
    l4_utcb_t * utcb = l4_utcb()) [inline], [noexcept]
```

Revoke rights from a task.

#### Parameters

<i>fpages</i>	An array of flexpages. Each item describes an area in one capability space of <code>this</code> task.
<i>num_fpages</i>	Number of fpages in the <code>fpages</code> array.
<i>map_mask</i>	Unmap mask, see <a href="#">l4_unmap_flags_t</a> .
<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. Defaults to <a href="#">l4_utcb</a> .

Revoke rights for an array of flexpages, see [unmap](#) for details.


#### Precondition

The caller needs to take care that `num_fpages` is not bigger than `L4_UTCB_GENERIC_DATA_SIZE - 2`.

Definition at line 154 of file [task](#).

References [L4::Kobject::cap\(\)](#).

Here is the call graph for this function:



The documentation for this class was generated from the following file:


- [l4/sys/task](#)

## 15.193 L4::Thread Class Reference


C++ [L4](#) kernel thread interface, see [Thread](#) for the C interface.

```
#include <thread>
```

Inheritance diagram for L4::Thread:



Collaboration diagram for L4::Thread:



## Data Structures

- class [Attr](#)  
*Thread* attributes used for *control()*.
- class [Modify\\_senders](#)  
*Class* wrapping a list of rules which modify the sender label of IPC messages inbound to this thread.

## Public Member Functions

- [l4\\_msgtag\\_t ex\\_regs](#) ([l4\\_addr\\_t ip](#), [l4\\_addr\\_t sp](#), [l4\\_umword\\_t flags](#), [l4\\_utcb\\_t \\*utcb=l4\\_utcb\(\)](#)) noexcept  
*Exchange basic thread registers.*
- [l4\\_msgtag\\_t ex\\_regs](#) ([l4\\_addr\\_t \\*ip](#), [l4\\_addr\\_t \\*sp](#), [l4\\_umword\\_t \\*flags](#), [l4\\_utcb\\_t \\*utcb=l4\\_utcb\(\)](#)) noexcept  
*Exchange basic thread registers and return previous values.*
- [l4\\_msgtag\\_t control](#) ([Attr](#) const &attr) noexcept  
*Commit the given thread-attributes object.*
- [l4\\_msgtag\\_t switch\\_to](#) ([l4\\_utcb\\_t \\*utcb=l4\\_utcb\(\)](#)) noexcept  
*Switch execution to this thread.*
- [l4\\_msgtag\\_t stats\\_time](#) ([l4\\_kernel\\_clock\\_t \\*us](#), [l4\\_utcb\\_t \\*utcb=l4\\_utcb\(\)](#)) noexcept  
*Get consumed time of thread in us.*
- [l4\\_msgtag\\_t vcpu\\_resume\\_start](#) ([l4\\_utcb\\_t \\*utcb=l4\\_utcb\(\)](#)) noexcept  
*Resume from vCPU asynchronous IPC handler, start.*
- [l4\\_msgtag\\_t vcpu\\_resume\\_commit](#) ([l4\\_msgtag\\_t tag](#), [l4\\_utcb\\_t \\*utcb=l4\\_utcb\(\)](#)) noexcept  
*Resume from vCPU asynchronous IPC handler, commit.*
- [l4\\_msgtag\\_t vcpu\\_control](#) ([l4\\_addr\\_t vcpu\\_state](#), [l4\\_utcb\\_t \\*utcb=l4\\_utcb\(\)](#)) noexcept  
*Enable the vCPU feature for the thread.*
- [l4\\_msgtag\\_t vcpu\\_control\\_ext](#) ([l4\\_addr\\_t ext\\_vcpu\\_state](#), [l4\\_utcb\\_t \\*utcb=l4\\_utcb\(\)](#)) noexcept  
*Enable the extended vCPU feature for the thread.*
- [l4\\_msgtag\\_t register\\_del\\_irq](#) ([Cap< Irq > irq](#), [l4\\_utcb\\_t \\*u=l4\\_utcb\(\)](#)) noexcept  
*Register an IRQ that will trigger upon deletion events.*
- [l4\\_msgtag\\_t modify\\_senders](#) ([Modify\\_senders](#) const &todo) noexcept  
*Apply sender modification rules.*
- [l4\\_msgtag\\_t register\\_doorbell\\_irq](#) ([Cap< Irq > irq](#), [l4\\_utcb\\_t \\*u=l4\\_utcb\(\)](#)) noexcept  
*Register an IRQ that will trigger when a forwarded virtual interrupt is pending.*

## Additional Inherited Members

### Protected Types inherited from

[L4::Kobject\\_t< Thread, Snd\\_destination, L4\\_PROTO\\_THREAD, Type\\_info::Demand\\_t< 1 > >](#)

- typedef [Thread](#) **Class**  
*The target interface type (inheriting from [Kobject\\_t](#)).*
- typedef [Typeid::Iface< PROTO, Thread >](#) **\_\_Iface**  
*The interface description for the derived class.*
- typedef [Typeid::Merge\\_list< Typeid::Iface\\_list< \\_\\_Iface >, typename Snd\\_destination::\\_\\_Iface\\_list >](#) **\_\_Iface\_list**  
*The list of all RPC interfaces provided directly or through inheritance.*

### Protected Member Functions inherited from

[L4::Kobject\\_t< Thread, Snd\\_destination, L4\\_PROTO\\_THREAD, Type\\_info::Demand\\_t< 1 > >](#)

- [L4::Cap< Class > c](#) () const noexcept  
*Get the capability to ourselves.*

### Static Protected Member Functions inherited from

[L4::Kobject\\_t< Thread, Snd\\_destination, L4\\_PROTO\\_THREAD, Type\\_info::Demand\\_t< 1 > >](#)

- static void [\\_\\_check\\_protocols](#)\_\_ () noexcept  
*Helper to check for protocol conflicts.*

### 15.193.1 Detailed Description

C++ [L4](#) kernel thread interface, see [Thread](#) for the C interface.

The [Thread](#) class defines a thread of execution in the [L4](#) context. Usually user-level and kernel threads are mapped 1:1 to each other. [Thread](#) kernel objects are created using a factory, see the [L4::Factory](#) API ([L4::Factory::create\(\)](#)).

Amongst other things an [L4::Thread](#) encapsulates:

- CPU state
  - General-purpose registers
  - Program counter
  - Stack pointer
- FPU state
- Scheduling parameters, see the [L4::Scheduler](#) API
- Execution state
  - Blocked, Runnable, Running

[Thread](#) objects provide an API for

- [Thread](#) configuration and manipulation
- [Thread](#) switching.

On ARM newly created threads run in EL0 by default and the exception level can be changed there with [ex\\_regs\(\)](#).

#### Include File

```
#include <l4/sys/thread>
```

For the C interface see the [Thread](#) API. For more elaborated documentation on the vCPU feature see [vCPU API](#).

Definition at line 52 of file [thread](#).

### 15.193.2 Member Function Documentation

#### 15.193.2.1 control()

```
l4_msgtag_t L4::Thread::control (
    Attr const & attr) [inline], [noexcept]
```

Commit the given thread-attributes object.

#### Parameters

<i>attr</i>	the attribute object to commit to the thread.
-------------	---

**Returns**

Syscall return tag containing one of the following return codes.

**Return values**

<code>L4_EOK</code>	Operation successful.
<code>-L4_EPERM</code>	Insufficient permissions; see precondition.
<code>-L4_EINVAL</code>	Malformed thread-attributes.

**Precondition**

The invoked [Thread](#) capability must have the permission [L4\\_CAP\\_FPAGE\\_S](#). When using [Attr::bind\(\)](#), also the respective [Task](#) capability must have the permission [L4\\_CAP\\_FPAGE\\_S](#).

Definition at line [243](#) of file [thread](#).

References [L4::Kobject::cap\(\)](#).

Here is the call graph for this function:

**15.193.2.2 ex\_regs() [1/2]**

```

l4_msgtag_t L4::Thread::ex_regs (
    l4_addr_t * ip,
    l4_addr_t * sp,
    l4_umword_t * flags,
    l4_utcb_t * utcb = l4_utcb()) [inline], [noexcept]
  
```

Exchange basic thread registers and return previous values.

**Parameters**

in, out	<i>ip</i>	New instruction pointer, use <code>~0UL</code> to leave the instruction pointer unchanged, return previous instruction pointer.
in, out	<i>sp</i>	New stack pointer, use <code>~0UL</code> to leave the stack pointer unchanged, returns previous stack pointer.
in, out	<i>flags</i>	Ex-regs flags, see <a href="#">L4_thread_ex_regs_flags</a> , return previous CPU flags of the thread.

	<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. Defaults to <a href="#">l4_utcb</a> .
--	-------------	--

### Returns

System call return tag. [out] parameters are only valid if the function returns successfully. Use [l4\\_error\(\)](#) to check.


This method allows to manipulate and start a thread. The basic functionality is to set the instruction pointer and the stack pointer of a thread. Additionally, this method allows also to cancel ongoing IPC operations and to force the thread to raise an artificial exception (see [flags](#)). If the thread is in an IPC operation or if [L4\\_THREAD\\_EX\\_REGS\\_TRIGGER\\_EXCEPTION](#) forces an IPC then changes in IP and SP take effect directly after returning from this IPC. On ARM this method allows to change the exception level, see [L4\\_thread\\_ex\\_regs\\_flags\\_arm](#) and [L4\\_thread\\_ex\\_regs\\_flags\\_arm64](#).

The thread is started using [L4::Scheduler::run\\_thread\(\)](#). However, if at the time [L4::Scheduler::run\\_thread\(\)](#) is called, the instruction pointer of the thread is invalid, a later call to [ex\\_regs\(\)](#) with a valid instruction pointer might start the thread.

Definition at line 119 of file [thread](#).

References [L4::Kobject::cap\(\)](#), and [l4\\_thread\\_ex\\_regs\\_ret\\_u\(\)](#).

Here is the call graph for this function:



### 15.193.2.3 ex\_regs() [2/2]

```

l4_msgtag_t L4::Thread::ex_regs (
    l4_addr_t ip,
    l4_addr_t sp,
    l4_umword_t flags,
    l4_utcb_t * utcb = l4_utcb()) [inline], [noexcept]

```

Exchange basic thread registers.

### Parameters

<i>ip</i>	New instruction pointer, use ~0UL to leave the instruction pointer unchanged.
<i>sp</i>	New stack pointer, use ~0UL to leave the stack pointer unchanged.
<i>flags</i>	Ex-regs flags, see <a href="#">L4_thread_ex_regs_flags</a> .
<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. Defaults to <a href="#">l4_utcb</a> .

**Returns**

System call return tag.


This method allows to manipulate and start a thread. The basic functionality is to set the instruction pointer and the stack pointer of a thread. Additionally, this method allows also to cancel ongoing IPC operations and to force the thread to raise an artificial exception (see `flags`). If the thread is in an IPC operation or if `L4_THREAD_EX_REGS_TRIGGER_EXCEPTION` forces an IPC then changes in IP and SP take effect directly after returning from this IPC. On ARM this method allows to change the exception level, see `L4_thread_ex_regs_flags_arm` and `L4_thread_ex_regs_flags_arm64`.

The thread is started using `L4::Scheduler::run_thread()`. However, if at the time `L4::Scheduler::run_thread()` is called, the instruction pointer of the thread is invalid, a later call to `ex_regs()` with a valid instruction pointer might start the thread.

Definition at line 84 of file `thread`.

References `L4::Kobject::cap()`, and `l4_thread_ex_regs_u()`.

Here is the call graph for this function:

**15.193.2.4 modify\_senders()**

```
l4_msgtag_t L4::Thread::modify_senders (
    Modify_senders const & todo) [inline], [noexcept]
```

Apply sender modification rules.

**Parameters**

<i>todo</i>	Prepared sender modification rules.
-------------	-------------------------------------

**Returns**

System call return tag.

The modification rules are applied to all IPCs to the thread (whether directly or by IPC gate) that are already in flight, that is that the sender is already blocking on.

See `Modify_senders` for a detailed description when applying sender modification rules is required.



**Note**

Modifying the senders of a thread running on a different CPU core is not supported.

To ensure that no in-flight senders are missed, either the thread itself must execute `modify_senders`, or the thread executing the `modify_senders` must synchronize with the target thread. This synchronization must ensure the following:

1. Before `modify_senders` is executed the target thread must execute at least shortly (so that pending DRQs are handled).
2. The target thread must pause its IPC dispatch, until `modify_senders` is completed. In other words, the target thread must not be receive ready, because otherwise an IPC message with an unmodified label can be transferred to its UTCB or vCPU state.


**See also**

[l4\\_thread\\_modify\\_sender\\_commit\(\)](#)

Definition at line 525 of file [thread](#).

References [L4::Kobject::cap\(\)](#), [l4\\_ipc\\_call\(\)](#), [L4\\_IPC\\_NEVER](#), [l4\\_msgtag\(\)](#), and [L4\\_PROTO\\_THREAD](#).

Here is the call graph for this function:

**15.193.2.5 register\_del\_irq()**

```

l4_msgtag_t L4::Thread::register_del_irq (
    Cap< Irq > irq,
    l4_utcb_t * u = l4_utcb()) [inline], [noexcept]

```

Register an IRQ that will trigger upon deletion events.

**Parameters**

<i>irq</i>	Capability selector for the IRQ object to be triggered.
<i>u</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. Defaults to <a href="#">l4_utcb</a> .

### Returns

System call return tag containing the return code.

### Return values

<code>-L4_BUSY</code>	A deletion IRQ is already bound to this thread.
<code>-L4_EPERM</code>	Insufficient permissions; see precondition.

### Precondition

The capability `irq` must have the permission `L4_CAP_FPAGE_W`.

In case the `irq` is already bound to an interrupt source, it is unbound first. When `irq` is deleted, it will be deregistered first. A registered deletion `irq` can only be deregistered by deleting the `irq` or the thread.

List of deletion events:

- deletion of one or several IPC gates bound to this thread.

When the deletion event is delivered, there is no indication about which IPC gate was deleted.


### See also

[l4\\_thread\\_register\\_del\\_irq](#)

Definition at line 427 of file [thread](#).

References [L4::Cap\\_base::cap\(\)](#), and [L4::Kobject::cap\(\)](#).

Here is the call graph for this function:



### 15.193.2.6 register\_doorbell\_irq()

```
l4_msgtag_t L4::Thread::register_doorbell_irq (
    Cap< Irq > irq,
    l4_utcb_t * u = l4_utcb()) [inline], [noexcept]
```

Register an IRQ that will trigger when a forwarded virtual interrupt is pending.

#### Parameters

<i>irq</i>	Capability selector for the IRQ object to be triggered.
<i>u</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. Defaults to <a href="#">l4_utcb</a> .

#### Returns

System call return tag containing the return code.

#### Return values

-L4_BUSY	A doorbell IRQ is already bound to this thread.
-L4_EPERM	Insufficient permissions; see precondition.

#### Precondition

The capability `irq` must have the permission [L4\\_CAP\\_FPAGE\\_W](#).

See [Irq::bind\\_vcpu\(\)](#) for more details about how interrupts can be forwarded directly by the kernel to extended vCPU user mode.

In case the `irq` is already bound to an interrupt source, it is unbound first. When `irq` is deleted, it will be deregistered first. A registered doorbell [irq](#) can only be deregistered by deleting the [irq](#) or the thread.


#### See also

[l4\\_thread\\_register\\_doorbell\\_irq](#)

Definition at line 553 of file [thread](#).

References [L4::Cap\\_base::cap\(\)](#), and [L4::Kobject::cap\(\)](#).

Here is the call graph for this function:



### 15.193.2.7 stats\_time()

```
l4_msgtag_t L4::Thread::stats_time (
    l4_kernel_clock_t * us,
    l4_utcb_t * utcb = l4_utcb()) [inline], [noexcept]
```

Get consumed time of thread in us.

#### Parameters

out	<i>us</i>	Consumed time in $\mu$ s.
	<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. Defaults to <a href="#">l4_utcb</a> .

#### Returns

Syscall return tag.

Definition at line [264](#) of file [thread](#).

References [L4::Kobject::cap\(\)](#).

Here is the call graph for this function:



### 15.193.2.8 switch\_to()

```
l4_msgtag_t L4::Thread::switch_to (
    l4_utcb_t * utcb = l4_utcb()) [inline], [noexcept]
```

Switch execution to this thread.

#### Parameters

<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. Defaults to <a href="#">l4_utcb</a> .
-------------	--

**Note**

The current time slice is inherited to this thread.

Definition at line 253 of file [thread](#).

References [L4::Kobject::cap\(\)](#).

Here is the call graph for this function:

**15.193.2.9 vcpu\_control()**

```

l4_msgtag_t L4::Thread::vcpu_control (
    l4_addr_t vcpu_state,
    l4_utcb_t * utcb = l4_utcb()) [inline], [noexcept]
  
```

Enable the vCPU feature for the thread.

**Parameters**

<i>vcpu_state</i>	A virtual address pointing to a <a href="#">l4_vcpu_state_t</a> . It must be a valid kernel-user-memory address (see <a href="#">L4::Task::add_ku_mem()</a> ).
<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. Defaults to <a href="#">l4_utcb</a> .

**Returns**

Syscall return tag.

This function enables the vCPU feature of `this` thread

The kernel-user memory starting at `vcpu_state` must be at least 128-byte aligned and must cover the size of [l4\\_vcpu\\_state\\_t](#).

The asynchronous IPC handling is described at [vCPU API](#).


**Note**

Disabling of the vCPU feature is optional and currently not supported.

Definition at line 358 of file [thread](#).

References [L4::Kobject::cap\(\)](#), and [l4\\_thread\\_vcpu\\_control\\_u\(\)](#).

Here is the call graph for this function:

**15.193.2.10 vcpu\_control\_ext()**

```

l4_msgtag_t L4::Thread::vcpu_control_ext (
    l4_addr_t ext_vcpu_state,
    l4_utcb_t * utcb = l4_utcb()) [inline], [noexcept]
  
```

Enable the extended vCPU feature for the thread.

**Parameters**

<i>ext_vcpu_state</i>	The virtual address where the kernel shall store the vCPU state in case of vCPU exits. The address must be a valid kernel-user-memory address (see <a href="#">L4::Task::add_ku_mem()</a> ).
<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. Defaults to <a href="#">l4_utcb</a> .

**Returns**

Syscall return tag.

The extended vCPU feature allows the use of hardware-virtualization features such as Intel's VT-x (VMX) or AMD's AMD-V (SVM).

This function enables the extended vCPU feature of `this` thread. Enabling the extended vCPU feature also enables the vCPU feature.

The kernel-user memory area starting at `ext_vcpu_state` must be at least 4 KiB aligned and must cover a size of `L4_PAGESIZE`. It includes the data of [l4\\_vcpu\\_state\\_t](#) at offset 0, the extended vCPU state at offset `L4_VCPU_OFFSET_EXT_STATE`, and, on some platforms, the extended vCPU information at offset `L4_VCPU_OFFSET_EXT_INFOS`.

On Intel's VT-x (VMX), the extended vCPU state is [l4\\_vm\\_vmx\\_vcpu\\_vmcs\\_t](#) and the extended vCPU information is [l4\\_vm\\_vmx\\_vcpu\\_infos\\_t](#). Furthermore, the extended vCPU state needs to be associated with a vCPU context (see [l4\\_vm\\_vmx\\_set\\_hw\\_vmcs\(\)](#)).

On AMD's AMD-V (SVM), the extended vCPU state is [l4\\_vm\\_svm\\_vmcb\\_t](#).

**Note**

Enabling the extended vCPU feature for a thread running on a different CPU core is currently not supported.


Disabling of the extended vCPU feature is currently not supported.

Upgrading from non-extended vCPU feature to extended vCPU feature is currently not supported.

Definition at line 398 of file [thread](#).

References [L4::Kobject::cap\(\)](#), and [l4\\_thread\\_vcpu\\_control\\_ext\\_u\(\)](#).

Here is the call graph for this function:

**15.193.2.11 vcpu\_resume\_commit()**

```

l4_msgtag_t L4::Thread::vcpu_resume_commit (
    l4_msgtag_t tag,
    l4_utcb_t * utcb = l4_utcb()) [inline], [noexcept]
  
```

Resume from vCPU asynchronous IPC handler, commit.

**Parameters**

<i>tag</i>	Tag to use, returned by <a href="#">l4_thread_vcpu_resume_start()</a> .
<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. Defaults to <a href="#">l4_utcb</a> .

**Returns**

Syscall return tag containing one of the following return codes.

**Return values**

0	Indicates a VM exit, provided that <code>thread</code> is in extended vCPU mode with virtual interrupts cleared.
1	Indicates an incoming IPC message, provided that the <code>thread</code> is in extended vCPU mode with virtual interrupts cleared.
-L4_EPERM	The user task capability set in the vCPU state is missing the <a href="#">L4_CAP_FPAGE_S</a> right. On Intel's VT-x (VMX): The vCPU context capability set in the extended vCPU state is missing the <a href="#">L4_CAP_FPAGE_S</a> right.
-L4_ENOENT	The user task capability set in the vCPU state is invalid.

<code>-L4_EINVAL</code>	<code>thread</code> is not the current running thread, or does not have the vCPU feature enabled. On Intel's VT-x (VMX): No vCPU context associated with the extended vCPU state.
<code>-L4_EBUSY</code>	On Intel's VT-x (VMX): The vCPU context associated with the extended vCPU state is already active on a different CPU.
<code>-L4_ENODEV</code>	On Intel's VT-x (VMX): The vCPU context associated with the extended vCPU state cannot be initialized or activated.
<code>&lt;0</code>	A supplied mapping failed.

All flexpages in the UTCB (added with [l4\\_sndfpage\\_add\(\)](#) after [l4\\_thread\\_vcpu\\_resume\\_start\(\)](#)) are unconditionally mapped into the user task configured in the vCPU state.

To resume into another address space, the capability to the target [Task](#) (or [L4::Vm](#)) must be set in [l4\\_vcpu\\_state\\_t::user\\_task](#) together with [L4\\_VCPU\\_F\\_USER\\_MODE](#). The capability selector must have all lower bits clear (see [L4\\_CAP\\_MASK](#)). The kernel adds the [L4\\_SYSF\\_SEND](#) flag there to indicate that the capability has been referenced in the kernel. Consecutive resumes will not reference the task capability again until all lower bits are cleared again. To release a task use a different task capability or use an invalid capability with the [L4\\_SYSF\\_REPLY](#) flag set.

The asynchronous IPC handling is described at [vCPU API](#).


See also

[l4\\_thread\\_vcpu\\_resume\\_commit](#)

Definition at line [334](#) of file [thread](#).

References [L4::Kobject::cap\(\)](#).

Here is the call graph for this function:



### 15.193.2.12 vcpu\_resume\_start()

```

l4_msgtag_t L4::Thread::vcpu_resume_start (
    l4_utcb_t * utcb = l4_utcb()) [inline], [noexcept]
  
```

Resume from vCPU asynchronous IPC handler, start.

#### Parameters



<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. Defaults to <a href="#">l4_utcb</a> .
-------------	--

**Returns**

Message tag to be used for [l4\\_sndfpage\\_add\(\)](#) and [l4\\_thread\\_vcpu\\_resume\\_commit\(\)](#)

The vCPU resume functionality is split in multiple functions to allow the specification of additional send-flexpages using [l4\\_sndfpage\\_add\(\)](#).

The asynchronous IPC handling is described at [vCPU API](#).

**See also**

[l4\\_thread\\_vcpu\\_resume\\_start](#)

Definition at line 283 of file [thread](#).

The documentation for this class was generated from the following file:

- [l4/sys/thread](#)

## 15.194 L4::Thread::Attr Class Reference

[Thread](#) attributes used for [control\(\)](#).

```
#include <thread>
```

Collaboration diagram for L4::Thread::Attr:

L4::Thread::Attr
<ul style="list-style-type: none"> <li>+ Attr()</li> <li>+ pager()</li> <li>+ pager()</li> <li>+ exc_handler()</li> <li>+ exc_handler()</li> <li>+ bind()</li> <li>+ alien()</li> </ul>

## Public Member Functions

- [Attr](#) ([l4\\_utcb\\_t](#) \*utcb=[l4\\_utcb](#)()) noexcept  
*Create a thread-attribute object with the given UTCB.*
- void [pager](#) ([Cap](#)< void > const &pager) noexcept  
*Set the pager capability selector.*
- [Cap](#)< void > [pager](#) () noexcept  
*Get the capability selector used for page-fault messages.*
- void [exc\\_handler](#) ([Cap](#)< void > const &exc\_handler) noexcept  
*Set the exception-handler capability selector.*
- [Cap](#)< void > [exc\\_handler](#) () noexcept  
*Get the capability selector used for exception messages.*
- void [bind](#) ([l4\\_utcb\\_t](#) \*thread\_utcb, [Cap](#)< [Task](#) > const &task) noexcept  
*Bind the thread to a task.*
- void [alien](#) (int on) noexcept  
*Enable alien mode.*

## Friends

- class [L4::Thread](#)

### 15.194.1 Detailed Description

[Thread](#) attributes used for [control\(\)](#).

This class is responsible for initializing various attributes of a thread in a UTCB for the [control\(\)](#) method.

#### Note

Instantiation of this class starts the preparation of the UTCB. Do not invoke any non-Attr functions between the instantiation and the call to [L4::Thread::control\(\)](#).

#### See also

[Thread control](#) for some more details.

Definition at line 137 of file [thread](#).

## 15.194.2 Constructor & Destructor Documentation

### 15.194.2.1 Attr()

```
L4::Thread::Attr::Attr (  
    l4_utcb_t * utcb = l4_utcb()) [inline], [explicit], [noexcept]
```

Create a thread-attribute object with the given UTCB.

#### Parameters

<i>utcb</i>	The UTCB to use for the later <a href="#">L4::Thread::control()</a> function. Usually this is the UTCB of the calling thread. See <a href="#">l4_utcb()</a> .
-------------	---

Definition at line 151 of file [thread](#).

## 15.194.3 Member Function Documentation

### 15.194.3.1 alien()

```
void L4::Thread::Attr::alien (  
    int on) [inline], [noexcept]
```

Enable alien mode.

#### Parameters

<i>on</i>	Boolean value defining the state of the feature.
-----------	--

For a thread in alien mode the kernel produces just an exception IPC for each IPC and exception caused by the alien thread instead of handling these events regularly. (Page faults of alien threads and interrupts occurring while the alien thread is running are always handled regularly.) While the alien thread is blocking, the exception handler can inspect and modify the state of the alien thread and potentially also the system call arguments. If the exception handler replies with [L4\\_PROTO\\_ALLOW\\_SYSCALL](#) as message tag, the kernel handles the next IPC or exception of the alien thread in a regular way. If the exception handler leaves certain thread state unchanged (in particular the instruction pointer), this will be the IPC or exception that caused the call of the exception handler. For a regularly processed IPC or exception of the alien thread the kernel also performs an exception IPC on kernel exit.

This feature can be used to attach a debugger to a thread and trace all object invocations and their results. It could also be used to handle other systems that use the same syscall instruction as [L4Re](#).

Definition at line 224 of file [thread](#).

### 15.194.3.2 bind()

```
void L4::Thread::Attr::bind (
    l4_utcb_t * thread_utcb,
    Cap< Task > const & task) [inline], [noexcept]
```

Bind the thread to a task.

#### Parameters

<i>thread_utcb</i>	The thread's UTCB address within the task it shall be bound to. The address must be aligned (architecture dependent; at least word aligned) and it must point to at least <a href="#">L4_UTCB_OFFSET</a> bytes of kernel-user memory.
<i>task</i>	The task the thread shall be bound to.

#### Precondition

The thread must not be bound to a task yet.

The capability `task` must have the permission [L4\\_CAP\\_FPAGE\\_S](#), otherwise the later call to [L4::Thread::control\(\)](#) with this [Attr](#) object will fail with [L4\\_EPERM](#).

A thread may execute code in the context of a task if and only if the thread is bound to the task. To actually start execution, [L4::Thread::ex\\_regs\(\)](#) needs to be used. Execution in the context of the task means that the code has access to all the task's resources (and only those). The executed code itself must be one of those resources. A thread can be bound at most once to a task.

#### Note

The UTCBs of different threads in the same task should not overlap in order to prevent data corruption.

Definition at line [218](#) of file [thread](#).

### 15.194.3.3 exc\_handler() [1/2]

```
Cap< void > L4::Thread::Attr::exc_handler () [inline], [noexcept]
```

Get the capability selector used for exception messages.

#### Returns

The capability selector used to send exception messages. The selector is valid in the task the thread is bound to.

Definition at line [189](#) of file [thread](#).

**15.194.3.4 exc\_handler()** [2/2]

```
void L4::Thread::Attr::exc_handler (
    Cap< void > const & exc_handler) [inline], [noexcept]
```

Set the exception-handler capability selector.

**Parameters**


<i>exc_handler</i>	The capability selector that shall be used for exception messages. This capability selector must be valid within the task the thread is bound to.
--------------------	---

Definition at line 180 of file [thread](#).


References [exc\\_handler\(\)](#).

Referenced by [exc\\_handler\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:

**15.194.3.5 pager()** [1/2]

```
Cap< void > L4::Thread::Attr::pager () [inline], [noexcept]
```

Get the capability selector used for page-fault messages.

**Returns**

The capability selector used to send page-fault messages. The selector is valid in the task the thread is bound to.

Definition at line 170 of file [thread](#).

### 15.194.3.6 pager() [2/2]

```
void L4::Thread::Attr::pager (
    Cap< void > const & pager) [inline], [noexcept]
```

Set the pager capability selector.

#### Parameters

<i>pager</i>	The capability selector that shall be used for page-fault messages. This capability selector must be valid within the task the thread is bound to.
--------------	--

Definition at line 161 of file [thread](#).

References [pager\(\)](#).

Referenced by [pager\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



The documentation for this class was generated from the following file:


- [l4/sys/thread](#)

## 15.195 L4::Thread::Modify\_senders Class Reference

[Class](#) wrapping a list of rules which modify the sender label of IPC messages inbound to this thread.

```
#include <thread>
```

Collaboration diagram for L4::Thread::Modify\_senders:



### Public Member Functions

- `int add(l4_umword_t match_mask, l4_umword_t match, l4_umword_t del_bits, l4_umword_t add_bits) noexcept`  
*Add a rule.*

### 15.195.1 Detailed Description

[Class](#) wrapping a list of rules which modify the sender label of IPC messages inbound to this thread.

Use the [add\(\)](#) function to add modification rules, and use [modify\\_senders\(\)](#) to commit. Do not use the UTCB in between as it is used by [add\(\)](#) and [modify\\_senders\(\)](#).

This mechanism shall be used to change the source object labels of every pending IPC of an IPC gate or an IRQ if the labels in such pending IPC become invalid for the receiving thread, potentially because:

- an IPC gate / IRQ was unbound from a thread, or
- an IPC gate / IRQ was removed, or
- the label of an IPC gate / IRQ bound to a thread was changed.

It is not required to perform the `modify_sender` mechanism after an IPC gate or an IRQ was bound to a thread for the first time.

Definition at line [448](#) of file [thread](#).

## 15.195.2 Member Function Documentation

### 15.195.2.1 add()

```
int L4::Thread::Modify_senders::add (
    l4_umword_t match_mask,
    l4_umword_t match,
    l4_umword_t del_bits,
    l4_umword_t add_bits) [inline], [noexcept]
```

Add a rule.

#### Parameters

<i>match_mask</i>	Bitmask of bits to match the label.
<i>match</i>	Bitmask that must be equal to the label after applying match_mask.
<i>del_bits</i>	Bits to be deleted from the label.
<i>add_bits</i>	Bits to be added to the label.

#### Returns

0 on success, <0 on error

In pseudo code: if ((sender\_label & match\_mask) == match) { sender\_label = (sender\_label & ~del\_bits) | add\_bits; }

Only the first match is applied.

#### See also


[l4\\_thread\\_modify\\_sender\\_add\(\)](#)

Definition at line 481 of file [thread](#).

References [L4\\_ENOMEM](#), and [l4\\_msg\\_regs\\_t::mr](#).

Referenced by [L4Re::Util::Object\\_registry::unregister\\_obj\(\)](#).

Here is the caller graph for this function:



The documentation for this class was generated from the following file:

- [l4/sys/thread](#)




## 15.196 L4::Thread\_group Class Reference


C++ [L4](#) kernel thread group interface, see [Thread groups](#) for the C interface.

```
#include <thread_group>
```

Inheritance diagram for L4::Thread\_group:



Collaboration diagram for L4::Thread\_group:



### Public Member Functions

- `l4_msgtag_t add (Cap< Thread > thread, l4_utcb_t *utcb=l4_utcb()) noexcept`  
Add thread to a thread group.
- `l4_msgtag_t remove (Cap< Thread > thread, l4_utcb_t *utcb=l4_utcb()) noexcept`  
Remove thread from a thread group.

### Additional Inherited Members

### Protected Types inherited from

**L4::Kobject\_t< Thread\_group, Snd\_destination, L4\_PROTO\_THREAD\_GROUP, Type\_info::Demand\_t<**

- typedef `Thread_group` **Class**

The target interface type (inheriting from [Kobject\\_t](#)).

- typedef Typeid::Iface< PROTO, [Thread\\_group](#) > \_\_Iface

The interface description for the derived class.

- typedef Typeid::Merge\_list< Typeid::Iface\_list< \_\_Iface >, typename Snd\_destination::\_\_Iface\_list > \_\_Iface\_list

The list of all RPC interfaces provided directly or through inheritance.

### Protected Member Functions inherited from

[L4::Kobject\\_t< Thread\\_group, Snd\\_destination, L4\\_PROTO\\_THREAD\\_GROUP, Type\\_info::Demand\\_t<](#)

- [L4::Cap< Class > c \(\)](#) const noexcept

Get the capability to ourselves.

### Static Protected Member Functions inherited from

[L4::Kobject\\_t< Thread\\_group, Snd\\_destination, L4\\_PROTO\\_THREAD\\_GROUP, Type\\_info::Demand\\_t<](#)

- static void [\\_\\_check\\_protocols\\_\\_ \(\)](#) noexcept

Helper to check for protocol conflicts.

## 15.196.1 Detailed Description

C++ [L4](#) kernel thread group interface, see [Thread groups](#) for the C interface.

An [L4](#) thread group is a collection of threads used as indirection for IPC gate and IRQ objects such that these objects can have multiple receivers, from which the kernel selects one according to a policy.

The primary use case for thread groups are multi-threaded servers and CPU core local IRQ / IPC delivery.

A thread can be bound to at most one thread group. Before binding a thread to a thread group, the thread must be bound to a task. All threads bound to the same thread group must belong to the same task.

Definition at line 34 of file [thread\\_group](#).

## 15.196.2 Member Function Documentation

### 15.196.2.1 add()

```
l4\_msgtag\_t L4::Thread_group::add (
    Cap< Thread > thread,
    l4\_utcb\_t * utcb = l4\_utcb\(\)) [inline], [noexcept]
```

Add thread to a thread group.

#### Parameters

<i>thread</i>	<a href="#">Thread</a> to add to the thread group.
<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. Defaults to <a href="#">l4_utcb</a> .

**Returns**

Syscall return tag containing one of the following return codes.


**Return values**

<i>L4_EOK</i>	No error occurred.
<i>-L4_EINVAL</i>	<code>thread</code> is not a thread object.
<i>-L4_EEXIST</i>	<code>thread</code> already bound to this thread group.
<i>-L4_EBUSY</i>	<code>thread</code> already bound to a different thread group.
<i>-L4_ENOENT</i>	<a href="#">Thread</a> group doesn't exist.

Definition at line 53 of file [thread\\_group](#).

References [L4::Cap\\_base::cap\(\)](#), and [L4::Kobject::cap\(\)](#).

Here is the call graph for this function:

**15.196.2.2 remove()**

```

14_msgtag_t L4::Thread_group::remove (
    Cap< Thread > thread,
    14_utcb_t * utcb = 14_utcb()) [inline], [noexcept]
  
```

Remove thread from a thread group.

**Parameters**

<i>thread</i>	<a href="#">Thread</a> to remove from the thread group.
<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. Defaults to <a href="#">14_utcb</a> .

**Returns**

Syscall return tag containing one of the following return codes.


**Return values**

<i>L4_EOK</i>	No error occurred.
<i>-L4_EINVAL</i>	<code>thread</code> is not a thread object.

Definition at line 67 of file [thread\\_group](#).

References [L4::Cap\\_base::cap\(\)](#), and [L4::Kobject::cap\(\)](#).

Here is the call graph for this function:



The documentation for this class was generated from the following file:


- [l4/sys/thread\\_group](#)

## 15.197 L4::Triggerable Struct Reference


Interface that allows an object to be triggered by some source.

```
#include <irq>
```

Inheritance diagram for L4::Triggerable:



Collaboration diagram for L4::Triggerable:



## Public Member Functions

- [l4\\_msgtag\\_t trigger](#) ([l4\\_utcb\\_t](#) \*utcb=[l4\\_utcb\(\)](#)) noexcept  
*Trigger the object.*

## Public Member Functions inherited from [L4::Irq\\_eoi](#)

- [l4\\_msgtag\\_t unmask](#) (unsigned irqnum, [l4\\_umword\\_t](#) \*label=0, [l4\\_timeout\\_t](#) to=[L4\\_IPC\\_NEVER](#), [l4\\_utcb\\_t](#) \*utcb=[l4\\_utcb\(\)](#)) noexcept  
*Unmask the given interrupt line.*

## Additional Inherited Members

## Protected Types inherited from [L4::Kobject\\_t< Triggerable, Irq\\_eoi, L4\\_PROTO\\_IRQ >](#)

- typedef [Triggerable](#) **Class**

*The target interface type (inheriting from [Kobject\\_t](#)).*

- `typedef Typeid::Iface< PROTO, Triggerable > __Iface`

*The interface description for the derived class.*

- `typedef Typeid::Merge_list< Typeid::Iface_list< \_\_Iface >, typename Irq_eoi::__Iface_list > \_\_Iface\_list`

*The list of all RPC interfaces provided directly or through inheritance.*

### Protected Member Functions inherited from [L4::Kobject\\_t< Triggerable, Irq\\_eoi, L4\\_PROTO\\_IRQ >](#)

- `L4::Cap< Class > c \(\) const noexcept`

*Get the capability to ourselves.*

### Static Protected Member Functions inherited from [L4::Kobject\\_t< Triggerable, Irq\\_eoi, L4\\_PROTO\\_IRQ >](#)

- `static void \_\_check\_protocols\_\_ \(\) noexcept`

*Helper to check for protocol conflicts.*

## 15.197.1 Detailed Description

Interface that allows an object to be triggered by some source.

The interface specifies no semantics for the trigger operation, this is defined by derived objects.

This interface is usually used in conjunction with [L4::lcu](#).

Definition at line 79 of file [irq](#).

## 15.197.2 Member Function Documentation

### 15.197.2.1 `trigger()`

```
l4\_msgtag\_t L4::Triggerable::trigger (
    l4\_utcb\_t * utcb = l4\_utcb\(\)) [inline], [noexcept]
```

Trigger the object.

#### Parameters

<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. See <a href="#">l4_utcb</a> .
-------------	--



## Returns


Syscall return tag for a send-only operation, this means there is no return value except [L4\\_MSGTAG\\_ERROR](#) indicating success or failure of the send operation. Use [l4\\_ipc\\_error\(\)](#) to check for errors and **do not** use [l4\\_error\(\)](#).

Definition at line 91 of file [irq](#).


References [L4::Kobject::cap\(\)](#), and [l4\\_irq\\_trigger\\_u\(\)](#).

Referenced by [L4::Semaphore::up\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



The documentation for this struct was generated from the following file:


- [l4/sys/irq](#)

## 15.198 L4::Type\_info Struct Reference

Dynamic Type Information for [L4Re](#) Interfaces.

```
#include <l4/sys/capability>
```

Collaboration diagram for L4::Type\_info:



## Data Structures

- class [Demand](#)  
*Data type for expressing the needed receive buffers at the server-side of an interface.*
- struct [Demand\\_t](#)  
*Template type statically describing demand of receive buffers.*
- struct [Demand\\_union\\_t](#)  
*Template type statically describing the combination of two [Demand](#) object.*

### 15.198.1 Detailed Description

Dynamic Type Information for [L4Re](#) Interfaces.

This class represents the runtime-dynamic type information for [L4Re](#) interfaces, and is not intended to be used directly by applications.

#### Note

The interface of is subject to changes.

The main use for this info is to be used by the implementation of the [L4::cap\\_dynamic\\_cast\(\)](#) function.

Definition at line [499](#) of file [\\_\\_typeinfo.h](#).

The documentation for this struct was generated from the following file:


- [l4/sys/\\_\\_typeinfo.h](#)

## 15.199 L4::Type\_info::Demand Class Reference

Data type for expressing the needed receive buffers at the server-side of an interface.

```
#include <l4/sys/capability>
```

Inheritance diagram for L4::Type\_info::Demand:



Collaboration diagram for L4::Type\_info::Demand:

L4::Type_info::Demand
+ caps
+ flags
+ mem
+ ports
+ Demand()
+ no_demand()
+ operator ()

### Public Member Functions

- [Demand](#) (unsigned char [caps](#)=0, unsigned char [flags](#)=0, unsigned char [mem](#)=0, unsigned char [ports](#)=0) noexcept  
*Make [Demand](#) object.*
- bool [no\\_demand](#) () const noexcept
- [Demand operator|](#) ([Demand](#) const &rhs) const noexcept  
*get the combined demand of this and rhs*

### Data Fields

- unsigned char **caps**  
*number of capability receive buffers.*
- unsigned char **flags**  
*flags, such as the need for timeouts (TBD).*
- unsigned char **mem**  
*number of memory receive buffers.*
- unsigned char **ports**  
*number of IO-port receive buffers.*

## 15.199.1 Detailed Description

Data type for expressing the needed receive buffers at the server-side of an interface.

Definition at line 506 of file [\\_\\_typeinfo.h](#).

## 15.199.2 Constructor & Destructor Documentation

### 15.199.2.1 Demand()

```
L4::Type_info::Demand::Demand (
    unsigned char caps = 0,
    unsigned char flags = 0,
    unsigned char mem = 0,
    unsigned char ports = 0) [inline], [explicit], [noexcept]
```

Make [Demand](#) object.

#### Parameters


<i>caps</i>	number of capability receive buffers
<i>flags</i>	flags, such as the need for timeouts (TBD).
<i>mem</i>	number of memory receive windows.
<i>ports</i>	number of IO-port receive windows.

Definition at line 527 of file [\\_\\_typeinfo.h](#).

References [caps](#), [flags](#), [mem](#), and [ports](#).

Referenced by [operator|\(\)](#).

Here is the caller graph for this function:



## 15.199.3 Member Function Documentation

### 15.199.3.1 no\_demand()

```
bool L4::Type_info::Demand::no_demand () const [inline], [noexcept]
```

### Returns


true if there is no demand at all

Definition at line 532 of file [\\_\\_typeinfo.h](#).

References [caps](#), [flags](#), [mem](#), and [ports](#).

Referenced by [L4::lpc\\_svr::Br\\_manager\\_no\\_buffers::alloc\\_buffer\\_demand\(\)](#).

Here is the caller graph for this function:



The documentation for this class was generated from the following file:


- [l4/sys/\\_\\_typeinfo.h](#)

## 15.200 L4::Type\_info::Demand\_t< CAPS, FLAGS, MEM, PORTS > Struct Template Reference


Template type statically describing demand of receive buffers.

```
#include <l4/sys/capability>
```

Inheritance diagram for L4::Type\_info::Demand\_t< CAPS, FLAGS, MEM, PORTS >:



Collaboration diagram for L4::Type\_info::Demand\_t< CAPS, FLAGS, MEM, PORTS >:



### Public Types

- enum { `Caps` = CAPS , `Flags` = FLAGS , `Mem` = MEM , `Ports` = PORTS }

### Additional Inherited Members

### Public Member Functions inherited from L4::Type\_info::Demand

- `Demand` (unsigned char `caps`=0, unsigned char `flags`=0, unsigned char `mem`=0, unsigned char `ports`=0) noexcept  
*Make `Demand` object.*
- bool `no_demand` () const noexcept
- `Demand operator|` (`Demand` const &rhs) const noexcept  
*get the combined demand of this and rhs*

### Data Fields inherited from L4::Type\_info::Demand

- unsigned char **caps**  
*number of capability receive buffers.*
- unsigned char **flags**  
*flags, such as the need for timeouts (TBD).*
- unsigned char **mem**  
*number of memory receive buffers.*
- unsigned char **ports**  
*number of IO-port receive buffers.*



### 15.200.1 Detailed Description

```
template<unsigned char CAPS = 0, unsigned char FLAGS = 0, unsigned char MEM = 0, unsigned char
PORTS = 0>
struct L4::Type_info::Demand_t< CAPS, FLAGS, MEM, PORTS >
```

Template type statically describing demand of receive buffers.

#### Template Parameters

<i>CAPS</i>	number of capability receive buffers needed.
<i>FLAGS</i>	flags, such as the need for timeouts (TBD).
<i>MEM</i>	number of memory receive windows needed.
<i>PORTS</i>	number of IO-port receive windwows needed.

Definition at line 553 of file [\\_\\_typeinfo.h](#).

### 15.200.2 Member Enumeration Documentation

#### 15.200.2.1 anonymous enum

```
template<unsigned char CAPS = 0, unsigned char FLAGS = 0, unsigned char MEM = 0, unsigned char
PORTS = 0>
anonymous enum
```

#### Enumerator

Caps	number of capability receive buffers.
Flags	flags, such as the need for timeouts.
Mem	number of memory receive windows.
Ports	number of IO-port receive windows.

Definition at line 555 of file [\\_\\_typeinfo.h](#).

The documentation for this struct was generated from the following file:


- [l4/sys/\\_\\_typeinfo.h](#)

## 15.201 L4::Type\_info::Demand\_union\_t< D1, D2 > Struct Template Reference


Template type statically describing the combination of two [Demand](#) object.

```
#include <l4/sys/capability>
```

Inheritance diagram for L4::Type\_info::Demand\_union\_t< D1, D2 >:



Collaboration diagram for L4::Type\_info::Demand\_union\_t< D1, D2 >:



## Additional Inherited Members

### Public Types inherited from

[L4::Type\\_info::Demand\\_t](#)< [\\_\\_l::Max](#)< [D1::Caps](#), [D2::Caps](#) >::Res, [D1::Flags](#)|[D2::Flags](#), [\\_\\_l::Max](#)< [D1::](#)

### Public Member Functions inherited from [L4::Type\\_info::Demand](#)

- [Demand](#) (unsigned char [caps](#)=0, unsigned char [flags](#)=0, unsigned char [mem](#)=0, unsigned char [ports](#)=0)  
noexcept  
*Make [Demand](#) object.*
- bool [no\\_demand](#) () const noexcept
- [Demand](#) operator| ([Demand](#) const &rhs) const noexcept  
*get the combined demand of this and rhs*

### Data Fields inherited from [L4::Type\\_info::Demand](#)

- unsigned char **caps**  
*number of capability receive buffers.*
- unsigned char **flags**  
*flags, such as the need for timeouts (TBD).*
- unsigned char **mem**  
*number of memory receive buffers.*
- unsigned char **ports**  
*number of IO-port receive buffers.*

## 15.201.1 Detailed Description

```
template<typename D1, typename D2>
struct L4::Type_info::Demand_union_t< D1, D2 >
```

Template type statically describing the combination of two [Demand](#) object.

### Template Parameters

<i>D1</i>	first demand object.
<i>D2</i>	second demand object.

Definition at line [573](#) of file [\\_\\_typeinfo.h](#).

The documentation for this struct was generated from the following file:


- [l4/sys/\\_\\_typeinfo.h](#)

## 15.202 L4::Typeid::Detail::\_Rpc< OPCODE, O, X > Struct Template Reference


Empty list of RPCs.

```
#include <__typeinfo.h>
```

Inheritance diagram for L4::Typeid::Detail::\_Rpc< OPCODE, O, X >:



Collaboration diagram for L4::Typeid::Detail::\_Rpc< OPCODE, O, X >:



### 15.202.1 Detailed Description

```
template<typename OPCODE, unsigned O, typename ... X>
struct L4::Typeid::Detail::_Rpc< OPCODE, O, X >
```

Empty list of RPCs.

Definition at line 365 of file [\\_\\_typeinfo.h](#).

The documentation for this struct was generated from the following file:


- [l4/sys/\\_\\_typeinfo.h](#)

## 15.203 L4::Typeid::Detail::\_Rpc< OPCODE, O, Default\_op< R > >::Rpc< Y > Struct Template Reference

Find the given RPC in the list.

```
#include <__typeinfo.h>
```

Collaboration diagram for L4::Typeid::Detail::\_Rpc< OPCODE, O, Default\_op< R > >::Rpc< Y >:



### 15.203.1 Detailed Description

```
template<typename OPCODE, unsigned O, typename R>
template<typename Y>
struct L4::Typeid::Detail::_Rpc< OPCODE, O, Default_op< R > >::Rpc< Y >
```

Find the given RPC in the list.

Definition at line 399 of file [\\_\\_typeinfo.h](#).

The documentation for this struct was generated from the following file:


- [l4/sys/\\_\\_typeinfo.h](#)

## 15.204 L4::Typeid::Detail::\_Rpc< OPCODE, O, R, X... > Struct Template Reference


Non-empty list of RPCs.

```
#include <__typeinfo.h>
```

Inheritance diagram for L4::Typeid::Detail::\_Rpc< OPCODE, O, R, X... >:



Collaboration diagram for L4::Typeid::Detail::\_Rpccs< OPCODE, O, R, X... >:



## Data Structures

- struct [Rpc](#)

*Find the given RPC in the list.*

## Public Types

- enum  
*The opcode value to use for this RPC, may be bogus if the [opcode\\_type](#) is void.*
- typedef [\\_Rpccs](#) **type**  
*The list element itself.*
- typedef OPCODE **opcode\_type**  
*The data type for the opcode.*
- typedef R **rpc**  
*The RPC type L4::lpc::Msg::Rpc\_call or L4::lpc::Msg::Rpc\_inline\_call.*
- typedef [\\_Rpccs](#)< OPCODE, \_Get\_opcode< R, O >::value+1, X... >::type **next**  
*The next RPC in the list or [Rpccs\\_end](#) if this is the last.*



### 15.204.1 Detailed Description

```
template<typename OPCODE, unsigned O, typename R, typename ... X>
struct L4::Typeid::Detail::_Rpc< OPCODE, O, R, X... >
```

Non-empty list of RPCs.

Definition at line 369 of file [\\_\\_typeinfo.h](#).

The documentation for this struct was generated from the following file:


- [l4/sys/\\_\\_typeinfo.h](#)

## 15.205 L4::Typeid::Detail::\_Rpc< OPCODE, O, R, X... >::Rpc< Y > Struct Template Reference

Find the given RPC in the list.

```
#include <__typeinfo.h>
```

Collaboration diagram for L4::Typeid::Detail::\_Rpc< OPCODE, O, R, X... >::Rpc< Y >:



### 15.205.1 Detailed Description

```
template<typename OPCODE, unsigned O, typename R, typename ... X>
template<typename Y>
struct L4::Typeid::Detail::_Rpc< OPCODE, O, R, X... >::Rpc< Y >
```

Find the given RPC in the list.

Definition at line 382 of file [\\_\\_typeinfo.h](#).

The documentation for this struct was generated from the following file:


- [l4/sys/\\_\\_typeinfo.h](#)

## 15.206 L4::Typeid::Detail::Rpccs\_end Struct Reference


Internal end-of-list marker.

```
#include <__typeinfo.h>
```

Inheritance diagram for L4::Typeid::Detail::Rpccs\_end:



Collaboration diagram for L4::Typeid::Detail::Rpccs\_end:



### 15.206.1 Detailed Description

Internal end-of-list marker.

Definition at line 317 of file [\\_\\_typeinfo.h](#).

The documentation for this struct was generated from the following file:


- [l4/sys/\\_\\_typeinfo.h](#)

## 15.207 L4::Typeid::P\_dispatch< LIST > Struct Template Reference

Use for protocol based dispatch stage.

```
#include <__typeinfo.h>
```

Collaboration diagram for L4::Typeid::P\_dispatch< LIST >:



### 15.207.1 Detailed Description

```
template<typename LIST>
struct L4::Typeid::P_dispatch< LIST >
```

Use for protocol based dispatch stage.

Definition at line 308 of file [\\_\\_typeinfo.h](#).

The documentation for this struct was generated from the following file:


- l4/sys/[\\_\\_typeinfo.h](#)

## 15.208 L4::Typeid::Raw\_ipc< CLASS > Struct Template Reference


RPCs list for passing raw incoming IPC to the server object.

```
#include <l4/sys/capability>
```

Inheritance diagram for L4::Typeid::Raw\_ipc< CLASS >:



Collaboration diagram for L4::Typeid::Raw\_ipc< CLASS >:



### 15.208.1 Detailed Description

```
template<typename CLASS>
struct L4::Typeid::Raw_ipc< CLASS >
```

RPCs list for passing raw incoming IPC to the server object.

#### Template Parameters

<b>CLASS</b>	The type of the interface (e.g., <a href="#">L4::lcu</a> )
--------------	--

This template allows to have fully handcrafted IPC protocols.

Definition at line 412 of file [\\_\\_typeinfo.h](#).

The documentation for this struct was generated from the following file:


- [l4/sys/\\_\\_typeinfo.h](#)

## 15.209 L4::Typeid::Rpc\_nocode< OPERATION > Struct Template Reference


List of RPCs of an interface using a single operation without an opcode.

```
#include <l4/sys/capability>
```

Inheritance diagram for L4::Typeid::Rpc\_nocode< OPERATION >:



Collaboration diagram for L4::Typeid::Rpc\_nocode< OPERATION >:



### 15.209.1 Detailed Description

```
template<typename OPERATION>
struct L4::Typeid::Rpc_nocode< OPERATION >
```

List of RPCs of an interface using a single operation without an opcode.

#### Template Parameters

<i>OPERATION</i>	The RPC operation as defined by L4_RPC etc.
------------------	---

Definition at line 454 of file [\\_\\_typeinfo.h](#).

The documentation for this struct was generated from the following file:


- [l4/sys/\\_\\_typeinfo.h](#)

## 15.210 L4::Typeid::Rpc< RPCS > Struct Template Reference


Standard list of RPCs of an interface.

```
#include <l4/sys/capability>
```

Inheritance diagram for L4::Typeid::Rpc< RPCS >:



Collaboration diagram for L4::Typeid::Rpc< RPCS >:



### 15.210.1 Detailed Description

```
template<typename ... RPCS>
struct L4::Typeid::Rpc< RPCS >
```

Standard list of RPCs of an interface.

#### Template Parameters

<i>RPCS</i>	list of RPC types as defined by L4_RPC etc.
-------------	---



This is the default list for RPC functions of an interface, it uses [L4::Opcode](#) as opcode type and uses opcodes starting from 0.

#### Examples

[examples/clntsrv/src/shared.h](#).

Definition at line 428 of file [\\_\\_typeinfo.h](#).

The documentation for this struct was generated from the following file:


- [l4/sys/\\_\\_typeinfo.h](#)

## 15.211 L4::Typeid::Rpc\_code< OPCODE\_TYPE > Struct Template Reference


List of RPCs of an interface using a special opcode type.

```
#include <l4/sys/capability>
```

Inheritance diagram for L4::Typeid::Rpc\_code< OPCODE\_TYPE >:



Collaboration diagram for L4::Typeid::Rpc\_code< OPCODE\_TYPE >:



## Data Structures

- struct [F](#)

### 15.211.1 Detailed Description

```
template<typename OPCODE_TYPE>
struct L4::Typeid::Rpc_code< OPCODE_TYPE >
```

List of RPCs of an interface using a special opcode type.

#### Template Parameters

<i>OPCODE_TYPE</i>	The data type of the opcode.
--------------------	------------------------------

List for RPC functions of an interface, using OPCODE\_TYPE as data type for the opcode, opcodes starting from 0.

Definition at line [439](#) of file [\\_\\_typeinfo.h](#).


The documentation for this struct was generated from the following file:

- [l4/sys/\\_\\_typeinfo.h](#)


## 15.212 L4::Typeid::Rpc\_code< OPCODE\_TYPE >::F< RPCS > Struct Template Reference

```
#include <__typeinfo.h>
```

Inheritance diagram for L4::Typeid::Rpc\_code< OPCODE\_TYPE >::F< RPCS >:



Collaboration diagram for L4::Typeid::Rpc\_code< OPCODE\_TYPE >::F< RPCS >:



### 15.212.1 Detailed Description

```

template<typename OPCODE_TYPE>
template<typename ... RPCS>
struct L4::Typeid::Rpc_code< OPCODE_TYPE >::F< RPCS >

```

#### Template Parameters

<i>RPCS</i>	list of RPC types as defined by L4_RPC etc.
-------------	---

Definition at line 445 of file [\\_\\_typeinfo.h](#).

The documentation for this struct was generated from the following file:


- [l4/sys/\\_\\_typeinfo.h](#)

## 15.213 L4::Typeid::Rpcsys< ARG > Struct Template Reference


List of RPCs typically used for kernel interfaces.

```
#include <l4/sys/capability>
```

Inheritance diagram for L4::Typeid::Rpcsys< ARG >:



Collaboration diagram for L4::Typeid::Rpcsys< ARG >:



### 15.213.1 Detailed Description

```
template<typename ... ARG>
struct L4::Typeid::Rpcsys< ARG >
```

List of RPCs typically used for kernel interfaces.

#### Template Parameters

<i>RPCS</i>	list of RPC types as defined by L4_RPC etc.
-------------	---

This list of RPC functions uses [l4\\_umword\\_t](#) as type for the opcode as most kernel protocol do.

Definition at line [465](#) of file [\\_\\_typeinfo.h](#).

The documentation for this struct was generated from the following file:


- [l4/sys/\\_\\_typeinfo.h](#)

## 15.214 L4::Types::\_\_Add\_rvalue\_reference\_helper< T, typename > Struct Template Reference


Helper template for [Add\\_rvalue\\_reference](#).

```
#include <types>
```

Inheritance diagram for L4::Types::\_\_Add\_rvalue\_reference\_helper< T, typename >:



Collaboration diagram for L4::Types::\_\_Add\_rvalue\_reference\_helper< T, typename >:



### 15.214.1 Detailed Description

```
template<typename T, typename = void>
struct L4::Types::__Add_rvalue_reference_helper< T, typename >
```

Helper template for [Add\\_rvalue\\_reference](#).

Definition at line 280 of file [types](#).

The documentation for this struct was generated from the following file:

- [l4/sys/cxx/types](#)


## 15.215 L4::Types::\_\_Add\_rvalue\_reference\_helper< T, Void< T && > > Struct Template Reference

Helper template for [Add\\_rvalue\\_reference](#).


```
#include <types>
```



Inheritance diagram for L4::Types::\_\_Add\_rvalue\_reference\_helper< T, Void< T && > >:



Collaboration diagram for L4::Types::\_\_Add\_rvalue\_reference\_helper< T, Void< T && > >:



### 15.215.1 Detailed Description

```
template<typename T>
struct L4::Types::__Add_rvalue_reference_helper< T, Void< T && > >
```

Helper template for [Add\\_rvalue\\_reference](#).

Definition at line 284 of file [types](#).

The documentation for this struct was generated from the following file:


- [l4/sys/cxx/types](#)

### 15.216 L4::Types::\_\_Underlying\_type\_helper< T, bool > Struct Template Reference


Helper template for [Underlying\\_type](#).

```
#include <types>
```

Inheritance diagram for L4::Types::\_\_Underlying\_type\_helper< T, bool >:



Collaboration diagram for L4::Types::\_\_Underlying\_type\_helper< T, bool >:



### 15.216.1 Detailed Description

```
template<typename T, bool = Is_enum<T>::value>
struct L4::Types::__Underlying_type_helper< T, bool >
```

Helper template for [Underlying\\_type](#).

#### Note

The implementation relies on the intrinsic `__underlying_type()` compiler type trait that is provided by the mainstream C++ compilers. There is no fully portable and future-proof way of implementing this template (the only fragile and unmaintainable possibility is to evaluate all possible underlying types).

#### Template Parameters

<i>T</i>	Enumeration type to get the underlying type of.
----------	---

Definition at line 359 of file [types](#).

The documentation for this struct was generated from the following file:


- [l4/sys/cxx/types](#)

## 15.217 L4::Types::\_\_Underlying\_type\_helper< T, false > Struct Template Reference


Helper template for [Underlying\\_type](#).

```
#include <types>
```

Inheritance diagram for L4::Types::\_\_Underlying\_type\_helper< T, false >:



Collaboration diagram for L4::Types::\_\_Underlying\_type\_helper< T, false >:



### 15.217.1 Detailed Description

```
template<typename T>
struct L4::Types::__Underlying_type_helper< T, false >
```

Helper template for [Underlying\\_type](#).

Definition at line 362 of file [types](#).

The documentation for this struct was generated from the following file:

- [l4/sys/cxx/types](#)

## 15.218 L4::Types::Add\_rvalue\_reference< T > Struct Template Reference

Create an rvalue reference of the given type.

```
#include <types>
```

Collaboration diagram for L4::Types::Add\_rvalue\_reference< T >:

L4::Types::Add_rvalue _reference< T >

### 15.218.1 Detailed Description

```
template<typename T>
struct L4::Types::Add_rvalue_reference< T >
```

Create an rvalue reference of the given type.

Definition at line 288 of file [types](#).

The documentation for this struct was generated from the following file:

- [l4/sys/cxx/types](#)



**Template Parameters**

V	The boolean value
---	-------------------

Definition at line [309](#) of file [types](#).

The documentation for this struct was generated from the following file:


- [l4/sys/cxx/types](#)

## 15.220 L4::Types::False Struct Reference

[False](#) meta value.


```
#include <types>
```

Inheritance diagram for L4::Types::False:





Collaboration diagram for L4::Types::False:



#### Additional Inherited Members

#### Public Types inherited from `L4::Types::Bool< false >`

- typedef `Bool< V >` **type**  
*The meta type itself.*

### 15.220.1 Detailed Description

`False` meta value.

Definition at line 317 of file `types`.

The documentation for this struct was generated from the following file:


- `l4/sys/cxx/types`

## 15.221 L4::Types::Flags< BITS\_ENUM, UNDERLYING > Class Template Reference

Template for defining typical [Flags](#) bitmaps.

```
#include <types>
```

Inheritance diagram for L4::Types::Flags< BITS\_ENUM, UNDERLYING >:



Collaboration diagram for L4::Types::Flags< BITS\_ENUM, UNDERLYING >:

L4::Types::Flags< BITS_ENUM, UNDERLYING >
<ul style="list-style-type: none"> <li>+ Flags()</li> <li>+ Flags()</li> <li>+ Flags()</li> <li>+ operator bool()</li> <li>+ operator!()</li> <li>+ operator =()</li> <li>+ operator =()</li> <li>+ operator&amp;=()</li> <li>+ operator&amp;=()</li> <li>+ operator~()</li> <li>+ clear()</li> <li>+ as_value()</li> <li>+ from_raw()</li> </ul>

## Public Types

- enum [None\\_type](#) { [None](#) }  
*The none type to get an empty bitmap.*
- typedef UNDERLYING **value\_type**  
*type of the underlying value*
- typedef BITS\_ENUM **bits\_enum\_type**  
*enum type defining a name for each bit*
- typedef Flags< BITS\_ENUM, UNDERLYING > **type**  
*the Flags<> type itself*

## Public Member Functions

- constexpr [Flags](#) ([None\\_type](#))  
*Make an empty bitmap.*
- constexpr **Flags** ()  
*Make default [Flags](#).*
- constexpr [Flags](#) (BITS\_ENUM e)  
*Make flags from bit name.*
- constexpr **operator bool** () const  
*Support for `if (flags)` syntax (test for non-empty flags).*

- constexpr bool **operator!** () const  
*Support for `if (!flags)` syntax (test for empty flags).*
- constexpr **type** & **operator|** = (type rhs)  
*Support `|` of two compatible [Flags](#) types.*
- constexpr **type** & **operator|** = (bits\_enum\_type rhs)  
*Support `|` of [Flags](#) type and bit name.*
- constexpr **type** & **operator&=** (type rhs)  
*Support `&=` of two compatible [Flags](#) types.*
- constexpr **type** & **operator&=** (bits\_enum\_type rhs)  
*Support `&=` of [Flags](#) type and bit name.*
- constexpr **type** **operator~** () const  
*Support `~` for [Flags](#) types.*
- constexpr **type** & **clear** (bits\_enum\_type flag)  
*Clear the given flag.*
- constexpr **value\_type** **as\_value** () const  
*Get the underlying value.*

### Static Public Member Functions

- static constexpr **type from\_raw** (value\_type v)  
*Make flags from a raw value of [value\\_type](#).*

### Friends

- constexpr **type operator|** (type lhs, type rhs)  
*Support `|` of two compatible [Flags](#) types.*
- constexpr **type operator|** (type lhs, bits\_enum\_type rhs)  
*Support `|` of [Flags](#) type and bit name.*
- constexpr **type operator&** (type lhs, type rhs)  
*Support `&` of two compatible [Flags](#) types.*
- constexpr **type operator&** (type lhs, bits\_enum\_type rhs)  
*Support `&` of [Flags](#) type and bit name.*

## 15.221.1 Detailed Description

```
template<typename BITS_ENUM, typename UNDERLYING = unsigned long>
class L4::Types::Flags< BITS_ENUM, UNDERLYING >
```

Template for defining typical [Flags](#) bitmaps.

### Template Parameters

<i>BITS_ENUM</i>	enum type that defines a name for each bit in the bitmap. The values of the enum members must be the number of the bit ( <i>not</i> a mask).
<i>UNDERLYING</i>	The underlying data type used to represent the bitmap.

The resulting data type provides a type-safe version that allows bitwise `and` and `or` operations with the `BITS_ENUM` members. As well as, test for `0` or `!0`.

Example:

```
enum Test_flag
{
    Do_weak_tests,
    Do_strong_tests
};

typedef L4::Types::Flags<Test_flag> Test_flags;

Test_flags x = Do_weak_tests;

if (x & Do_strong_tests) { ... }
x |= Do_strong_tests;
if (x & Do_strong_tests) { ... }
```

Definition at line 52 of file [types](#).

## 15.221.2 Member Enumeration Documentation

### 15.221.2.1 None\_type

```
template<typename BITS_ENUM, typename UNDERLYING = unsigned long>
enum L4::Types::Flags::None_type
```

The none type to get an empty bitmap.

#### Enumerator

None	Use this to get an empty bitmap.
------	----------------------------------

Definition at line 68 of file [types](#).

## 15.221.3 Constructor & Destructor Documentation

### 15.221.3.1 Flags() [1/2]

```
template<typename BITS_ENUM, typename UNDERLYING = unsigned long>
L4::Types::Flags< BITS_ENUM, UNDERLYING >::Flags (
    None_type ) [inline], [constexpr]
```

Make an empty bitmap.

Usually used for implicit conversion from [Flags::None](#).

```
Flags x = Flags::None;
```

Definition at line 78 of file [types](#).

### 15.221.3.2 Flags() [2/2]

```
template<typename BITS_ENUM, typename UNDERLYING = unsigned long>
L4::Types::Flags< BITS_ENUM, UNDERLYING >::Flags (
    BITS_ENUM e) [inline], [constexpr]
```

Make flags from bit name.

Usually used for implicit conversion for a bit name.

```
Test_flags f = Do_strong_tests;
```

Definition at line 91 of file [types](#).

## 15.221.4 Member Function Documentation

### 15.221.4.1 clear()

```
template<typename BITS_ENUM, typename UNDERLYING = unsigned long>
type & L4::Types::Flags< BITS_ENUM, UNDERLYING >::clear (
    bits_enum_type flag) [inline], [constexpr]
```

Clear the given flag.

#### Parameters

<i>flag</i>	The flag that shall be cleared.
-------------	---------------------------------

`flags.clear(The_flag)` is a shortcut for `flags &= ~Flags(The_flag)`.

Definition at line 146 of file [types](#).

### 15.221.4.2 from\_raw()

```
template<typename BITS_ENUM, typename UNDERLYING = unsigned long>
constexpr type L4::Types::Flags< BITS_ENUM, UNDERLYING >::from_raw (
    value_type v) [inline], [static], [constexpr]
```

Make flags from a raw value of [value\\_type](#).

This function may be used for example in C wrapper code.

Definition at line 98 of file [types](#).

The documentation for this class was generated from the following file:


- [l4/sys/cxx/types](#)

## 15.222 L4::Types::Flags\_ops\_t< DT > Struct Template Reference

Mixin class to define a set of friend bitwise operators on `DT`.

```
#include <types>
```

Inheritance diagram for L4::Types::Flags\_ops\_t< DT >:



Collaboration diagram for L4::Types::Flags\_ops\_t< DT >:

L4::Types::Flags_ops_t< DT >
<ul style="list-style-type: none"> <li>+ operator =( )</li> <li>+ operator&amp;=( )</li> <li>+ operator-=( )</li> <li>+ operator bool( )</li> <li>+ operator~( )</li> </ul>

## Public Member Functions

- constexpr DT & **operator|**=( DT const r)  
*bitwise or assignment for DT*
- constexpr DT & **operator&=** (DT const r)  
*bitwise and assignment for DT*
- constexpr DT & **operator-=** (DT const r)  
*Bitwise difference (clear bits) assignment for DT.*
- constexpr **operator bool** ( ) const  
*explicit conversion to bool for tests*
- constexpr DT **operator~** ( ) const  
*bitwise negation for DT*

## Friends

- constexpr DT **operator|** (DT l, DT r)  
*bitwise or for DT*
- constexpr DT **operator&** (DT l, DT r)  
*bitwise and for DT*
- constexpr DT **operator-** (DT l, DT r)  
*Bitwise difference (clear bits) for DT.*
- constexpr bool **operator==** (DT l, DT r)  
*equality for DT*
- constexpr bool **operator!=** (DT l, DT r)  
*inequality for DT*



### 15.222.1 Detailed Description

```
template<typename DT>
struct L4::Types::Flags_ops_t< DT >
```

Mixin class to define a set of friend bitwise operators on `DT`.

#### Template Parameters

<i>DT</i>	The type usually inheriting from <a href="#">Flags_ops_t</a> with a member <i>raw</i> of enum or integral type.
-----------	---

Definition at line 200 of file [types](#).

The documentation for this struct was generated from the following file:


- [l4/sys/cxx/types](#)

## 15.223 L4::Types::Flags\_t< DT, T > Struct Template Reference


Template type to define a flags type with bitwise operations.

```
#include <types>
```

Inheritance diagram for L4::Types::Flags\_t< DT, T >:



Collaboration diagram for L4::Types::Flags\_t< DT, T >:



### Public Member Functions

- constexpr **Flags\_t** ()=default  
*Default (uninitializing) constructor.*
- constexpr **Flags\_t** (DT f)  
*Initialization from determinator type.*
- constexpr **Flags\_t** (T f)  
*Explicit initialization from the underlying type.*

## Public Member Functions inherited from [L4::Types::Flags\\_ops\\_t< Flags\\_t< DT, T > >](#)

- constexpr DT & **operator**|= (DT const r)  
*bitwise or assignment for DT*
- constexpr DT & **operator**&= (DT const r)  
*bitwise and assignment for DT*
- constexpr DT & **operator**-= (DT const r)  
*Bitwise difference (clear bits) assignment for DT.*
- constexpr **operator** bool () const  
*explicit conversion to bool for tests*
- constexpr DT **operator**~ () const  
*bitwise negation for DT*

## Data Fields

- T **raw** = 0  
*Raw integral value.*

## Static Public Attributes

- static constexpr [Flags\\_t](#) **None** = [Flags\\_t](#)()  
*Empty flags literal.*

## 15.223.1 Detailed Description

```
template<typename DT, typename T>
struct L4::Types::Flags_t< DT, T >
```

Template type to define a flags type with bitwise operations.

### Template Parameters

<i>DT</i>	determinator type to make the resulting type unique (unused).
<i>T</i>	underlying type used to store the bits, usually an integral type.

Definition at line [261](#) of file [types](#).


The documentation for this struct was generated from the following file:

- [l4/sys/cxx/types](#)


## 15.224 L4::Types::Int\_for\_size< SIZE, bool > Struct Template Reference

Metafunction to get an unsigned integral type for the given size.

Inheritance diagram for L4::Types::Int\_for\_size< SIZE, bool >:



Collaboration diagram for L4::Types::Int\_for\_size< SIZE, bool >:



### 15.224.1 Detailed Description

```
template<unsigned SIZE, bool = true>
struct L4::Types::Int_for_size< SIZE, bool >
```

Metafunction to get an unsigned integral type for the given size.

**Template Parameters**

<i>SIZE</i>	The size of the integer in bytes.
-------------	-----------------------------------

Definition at line 158 of file [types](#).

The documentation for this struct was generated from the following file:


- [l4/sys/cxx/types](#)

**15.225 L4::Types::Int\_for\_type< T > Struct Template Reference**

Metafunction to get an integral type of the same size as *T*.

```
#include <types>
```

Collaboration diagram for L4::Types::Int\_for\_type< T >:

**Public Types**

- typedef [Int\\_for\\_size](#)< sizeof(T)>::type **type**  
*The resulting unsigned integer type with the size like *T*.*

**15.225.1 Detailed Description**

```
template<typename T>
struct L4::Types::Int_for_type< T >
```

Metafunction to get an integral type of the same size as *T*.

**Template Parameters**

<i>T</i>	The type for which an unsigned integral type with the same size is needed.
----------	--

Definition at line 185 of file [types](#).

The documentation for this struct was generated from the following file:


- [l4/sys/cxx/types](#)

## 15.226 L4::Types::Integral\_constant< T, Value > Struct Template Reference


Wrapper for a static constant of the given type.

```
#include <types>
```

Inheritance diagram for L4::Types::Integral\_constant< T, Value >:



Collaboration diagram for L4::Types::Integral\_constant< T, Value >:



### 15.226.1 Detailed Description

```
template<typename T, T Value>
struct L4::Types::Integral_constant< T, Value >
```

Wrapper for a static constant of the given type.

Definition at line 325 of file [types](#).

The documentation for this struct was generated from the following file:


- [l4/sys/cxx/types](#)

## 15.227 L4::Types::ls\_enum< T > Struct Template Reference

Check whether the given type is an enumeration type.


```
#include <types>
```

Inheritance diagram for L4::Types::ls\_enum< T >:





Collaboration diagram for L4::Types::ls\_enum< T >:



### 15.227.1 Detailed Description

```
template<typename T>
struct L4::Types::ls_enum< T >
```

Check whether the given type is an enumeration type.

#### Note

The implementation relies on the intrinsic `__is_enum()` compiler type trait that is provided by the mainstream C++ compilers. There is no fully portable and future-proof way of implementing this template (the only fragile and unmaintainable possibility is to exclude all other types to identify the enumeration type).

#### Template Parameters

<i>T</i>	Type to check whether it is an enumeration type.
----------	--

Definition at line 345 of file [types](#).

The documentation for this struct was generated from the following file:


- [I4/sys/cxx/types](#)

## 15.228 L4::Types::Same< A, B > Struct Template Reference


Compare two data types for equality.

```
#include <types>
```

Inheritance diagram for L4::Types::Same< A, B >:



Collaboration diagram for L4::Types::Same< A, B >:



#### Additional Inherited Members

#### Public Types inherited from **L4::Types::Bool< false >**

- typedef **Bool< V >** **type**  
*The meta type itself.*

### 15.228.1 Detailed Description

```
template<typename A, typename B>
struct L4::Types::Same< A, B >
```

Compare two data types for equality.

**Template Parameters**

<i>A</i>	The first data type
<i>B</i>	The second data type

The result is the boolean [True](#) if A and B are the same types.

Definition at line [381](#) of file [types](#).

The documentation for this struct was generated from the following file:


- [l4/sys/cxx/types](#)

## 15.229 L4::Types::True Struct Reference


[True](#) meta value.

```
#include <types>
```

Inheritance diagram for L4::Types::True:



Collaboration diagram for L4::Types::True:



#### Additional Inherited Members

#### Public Types inherited from `L4::Types::Bool< true >`

- typedef `Bool< V >` **type**  
*The meta type itself.*

#### 15.229.1 Detailed Description

`True` meta value.

Definition at line 321 of file `types`.

The documentation for this struct was generated from the following file:


- `l4/sys/cxx/types`

## 15.230 L4::Types::\_\_Underlying\_type< T > Struct Template Reference


Get an underlying type of an enumeration type.

```
#include <types>
```

Inheritance diagram for L4::Types::\_\_Underlying\_type< T >:



Collaboration diagram for L4::Types::\_\_Underlying\_type< T >:



### 15.230.1 Detailed Description

```
template<typename T>  
struct L4::Types::Underlying_type< T >
```

Get an underlying type of an enumeration type.

Definition at line 365 of file [types](#).

The documentation for this struct was generated from the following file:

- [l4/sys/cxx/types](#)


## 15.231 L4::Uart Class Reference

[Uart](#) driver abstraction.

```
#include <uart_base.h>
```



Inheritance diagram for L4::Uart:



Collaboration diagram for L4::Uart:

L4::Uart
<ul style="list-style-type: none"> <li>+ startup()</li> <li>+ shutdown()</li> <li>+ change_mode()</li> <li>+ write()</li> <li>+ mode()</li> <li>+ rate()</li> <li>+ enable_rx_irq()</li> <li>+ irq_ack()</li> <li>+ char_avail()</li> <li>+ get_char()</li> <li># generic_write()</li> </ul>

## Public Member Functions

- virtual bool [startup](#) (Io\_register\_block const \*regs)=0  
*Start the UART driver.*
- virtual void [shutdown](#) ()=0  
*Terminate the UART driver.*
- virtual bool [change\\_mode](#) (Transfer\_mode m, Baud\_rate r)=0  
*Set certain parameters of the UART.*
- virtual int [write](#) (char const \*s, unsigned long count, bool blocking=true) const =0  
*Transmit a number of characters.*
- Transfer\_mode [mode](#) () const  
*Return the transfer mode.*
- Baud\_rate [rate](#) () const  
*Return the baud rate.*
- virtual bool [enable\\_rx\\_irq](#) (bool=true)  
*Enable the receive IRQ.*
- virtual void [irq\\_ack](#) ()  
*Acknowledge a received interrupt.*
- virtual int [char\\_avail](#) () const =0  
*Check if there is at least one character available for reading from the UART.*
- virtual int [get\\_char](#) (bool blocking=true) const =0  
*Read a character from the UART.*

## Protected Member Functions

- `template<typename Uart_driver, bool Timeout_guard = true>`  
`int generic_write (char const *s, unsigned long count, bool blocking=true) const`  
*Internal function transmitting each character one-after-another and finally waiting that the transmission did actually finish.*

### 15.231.1 Detailed Description

[Uart](#) driver abstraction.

Definition at line 21 of file [uart\\_base.h](#).

### 15.231.2 Member Function Documentation

#### 15.231.2.1 change\_mode()

```
virtual bool L4::Uart::change_mode (
    Transfer_mode m,
    Baud_rate r) [pure virtual]
```

Set certain parameters of the UART.

#### Parameters

<i>m</i>	UART mode. Depends on the hardware.
<i>r</i>	Baud rate.

#### Return values

<i>true</i>	Mode setting succeeded (or was not performed at all).
<i>false</i>	Mode setting failed for some reason.

#### Note

Some drivers don't perform any mode setting at all and just return true.

Implemented in [L4::Uart\\_apb](#).

#### 15.231.2.2 char\_avail()

```
virtual int L4::Uart::char_avail () const [pure virtual]
```

Check if there is at least one character available for reading from the UART.

#### Returns

0 if there is no character available for reading, !=0 otherwise.

Implemented in [L4::Uart\\_apb](#).

### 15.231.2.3 enable\_rx\_irq()

```
virtual bool L4::Uart::enable_rx_irq (
    bool = true) [inline], [virtual]
```

Enable the receive IRQ.

#### Return values

<i>true</i>	The RX IRQ was successfully enabled / disabled.
<i>false</i>	The RX IRQ couldn't be enabled / disabled. The driver does not support this operation.

Reimplemented in [L4::Uart\\_apb](#).

Definition at line 104 of file [uart\\_base.h](#).

### 15.231.2.4 generic\_write()

```
template<typename Uart_driver, bool Timeout_guard = true>
int L4::Uart::generic_write (
    char const * s,
    unsigned long count,
    bool blocking = true) const [inline], [protected]
```

Internal function transmitting each character one-after-another and finally waiting that the transmission did actually finish.

#### Parameters

<i>s</i>	<a href="#">Buffer</a> containing the characters.
<i>count</i>	The number of characters to transmit.
<i>blocking</i>	If true, wait until there is space in the transmit buffer and also wait until every character was successful transmitted. Otherwise do not wait.

#### Returns

The number of successful written characters.

Definition at line 144 of file [uart\\_base.h](#).

References [L4::Poll\\_timeout\\_counter::test\(\)](#).

Here is the call graph for this function:



### 15.231.2.5 get\_char()

```
virtual int L4::Uart::get_char (
    bool blocking = true) const [pure virtual]
```

Read a character from the UART.

#### Parameters

<i>blocking</i>	If true, wait until a character is available for reading. Otherwise do not wait and just return -1 if no character is available.
-----------------	--

#### Returns

The actual character read from the UART.

Implemented in [L4::Uart\\_apb](#).

### 15.231.2.6 mode()

```
Transfer_mode L4::Uart::mode () const [inline]
```

Return the transfer mode.

#### Returns

The transfer mode.

Definition at line [86](#) of file [uart\\_base.h](#).

### 15.231.2.7 rate()

```
Baud_rate L4::Uart::rate () const [inline]
```

Return the baud rate.

#### Returns

The baud rate.

Definition at line [93](#) of file [uart\\_base.h](#).

### 15.231.2.8 shutdown()

```
virtual void L4::Uart::shutdown () [pure virtual]
```

Terminate the UART driver.

This includes disabling of interrupts.

Implemented in [L4::Uart\\_apb](#).

### 15.231.2.9 startup()

```
virtual bool L4::Uart::startup (
    Io_register_block const * regs) [pure virtual]
```

Start the UART driver.

#### Parameters

<i>regs</i>	IO register block of the UART.
-------------	--------------------------------

#### Return values

<i>true</i>	Startup succeeded.
<i>false</i>	Startup failed.

Implemented in [L4::Uart\\_apb](#).

### 15.231.2.10 write()

```
virtual int L4::Uart::write (
    char const * s,
    unsigned long count,
    bool blocking = true) const [pure virtual]
```

Transmit a number of characters.

#### Parameters

<i>s</i>	<a href="#">Buffer</a> containing the characters.
<i>count</i>	Number of characters to transmit.
<i>blocking</i>	If true, wait until there is space in the transmit buffer and also wait until every character was successful transmitted. Otherwise do not wait.

#### Returns

The number of successfully written characters.

Implemented in [L4::Uart\\_apb](#).

The documentation for this class was generated from the following file:


- pkg/drivers-frst/uart/include/uart\_base.h

## 15.232 L4::Uart\_apb Class Reference


Driver for the Advanced Peripheral Bus (APB) UART from the Cortex-M System Design Kit (CMSDK).

```
#include <uart_apb.h>
```

Inheritance diagram for L4::Uart\_apb:



Collaboration diagram for L4::Uart\_apb:



## Public Member Functions

- **Uart\_apb** (unsigned freq)  
*freq == 0 means unknown and don't change baud rate*
- bool **startup** (lo\_register\_block const \*) override  
*Start the UART driver.*
- void **shutdown** () override  
*Terminate the UART driver.*
- bool **change\_mode** (Transfer\_mode m, Baud\_rate r) override  
*Set certain parameters of the UART.*



- int [write](#) (char const \*s, unsigned long count, bool blocking=true) const override  
*Transmit a number of characters.*
- bool [enable\\_rx\\_irq](#) (bool enable) override  
*Enable the receive IRQ.*
- int [char\\_avail](#) () const override  
*Check if there is at least one character available for reading from the UART.*
- int [get\\_char](#) (bool blocking=true) const override  
*Read a character from the UART.*

## Public Member Functions inherited from [L4::Uart](#)

- Transfer\_mode [mode](#) () const  
*Return the transfer mode.*
- Baud\_rate [rate](#) () const  
*Return the baud rate.*
- virtual void [irq\\_ack](#) ()  
*Acknowledge a received interrupt.*

## Additional Inherited Members

## Protected Member Functions inherited from [L4::Uart](#)

- template<typename Uart\_driver, bool Timeout\_guard = true>  
int [generic\\_write](#) (char const \*s, unsigned long count, bool blocking=true) const  
*Internal function transmitting each character one-after-another and finally waiting that the transmission did actually finish.*

### 15.232.1 Detailed Description

Driver for the Advanced Peripheral Bus (APB) UART from the Cortex-M System Design Kit (CMSDK).

Definition at line 17 of file [uart\\_apb.h](#).

### 15.232.2 Member Function Documentation

#### 15.232.2.1 [change\\_mode\(\)](#)

```
bool L4::Uart_apb::change_mode (
    Transfer_mode m,
    Baud_rate r) [override], [virtual]
```

Set certain parameters of the UART.

#### Parameters

<i>m</i>	UART mode. Depends on the hardware.
----------	-------------------------------------

<i>r</i>	Baud rate.
----------	------------

**Return values**

<i>true</i>	Mode setting succeeded (or was not performed at all).
<i>false</i>	Mode setting failed for some reason.

**Note**

Some drivers don't perform any mode setting at all and just return true.

Implements [L4::Uart](#).

**15.232.2.2 char\_avail()**

```
int L4::Uart_apb::char_avail () const [override], [virtual]
```

Check if there is at least one character available for reading from the UART.

**Returns**

0 if there is no character available for reading, !=0 otherwise.

Implements [L4::Uart](#).

**15.232.2.3 enable\_rx\_irq()**

```
bool L4::Uart_apb::enable_rx_irq (  
    bool ) [override], [virtual]
```

Enable the receive IRQ.

**Return values**

<i>true</i>	The RX IRQ was successfully enabled / disabled.
<i>false</i>	The RX IRQ couldn't be enabled / disabled. The driver does not support this operation.

Reimplemented from [L4::Uart](#).

#### 15.232.2.4 get\_char()

```
int L4::Uart_apb::get_char (
    bool blocking = true) const [override], [virtual]
```

Read a character from the UART.

##### Parameters

<i>blocking</i>	If true, wait until a character is available for reading. Otherwise do not wait and just return -1 if no character is available.
-----------------	--

##### Returns

The actual character read from the UART.

Implements [L4::Uart](#).

#### 15.232.2.5 shutdown()

```
void L4::Uart_apb::shutdown () [override], [virtual]
```

Terminate the UART driver.

This includes disabling of interrupts.

Implements [L4::Uart](#).

#### 15.232.2.6 startup()

```
bool L4::Uart_apb::startup (
    Io_register_block const * regs) [override], [virtual]
```

Start the UART driver.

##### Parameters

<i>regs</i>	IO register block of the UART.
-------------	--------------------------------

##### Return values

<i>true</i>	Startup succeeded.
<i>false</i>	Startup failed.

Implements [L4::Uart](#).

### 15.232.2.7 write()

```
int L4::Uart_apb::write (  
    char const * s,  
    unsigned long count,  
    bool blocking = true) const [override], [virtual]
```

Transmit a number of characters.

#### Parameters

<i>s</i>	<a href="#">Buffer</a> containing the characters.
<i>count</i>	Number of characters to transmit.
<i>blocking</i>	If true, wait until there is space in the transmit buffer and also wait until every character was successful transmitted. Otherwise do not wait.

#### Returns

The number of successfully written characters.

Implements [L4::Uart](#).

The documentation for this class was generated from the following file:


- pkg/drivers-frst/uart/include/uart\_apb.h

## 15.233 L4::Unknown\_error Class Reference


[Exception](#) for an unknown condition.

```
#include <l4/cxx/exceptions>
```

Inheritance diagram for L4::Unknown\_error:



Collaboration diagram for L4::Unknown\_error:



### Public Member Functions

- `char const * str ()` `const noexcept` override  
*Return a human readable string for the exception.*

### Public Member Functions inherited from [L4::Base\\_exception](#)

- `virtual ~Base_exception ()` `noexcept`  
*Destruction.*

### Public Member Functions inherited from [L4::Exception\\_tracer](#)

- `void const *const * pc_array ()` `const noexcept`  
*Get the array containing the call trace.*
- `int frame_count ()` `const noexcept`  
*Get the number of entries that are valid in the call trace.*

## Additional Inherited Members

### Protected Member Functions inherited from [L4::Base\\_exception](#)

- **Base\_exception** () noexcept  
*Create a base exception.*

### Protected Member Functions inherited from [L4::Exception\\_tracer](#)

- **Exception\_tracer** () noexcept  
*Create a back trace.*

## 15.233.1 Detailed Description

[Exception](#) for an unknown condition.

This error is usually used when a server returns an unknown return state to the client, this may indicate incompatible messages used by the client and the server.

Definition at line 208 of file [exceptions](#).

The documentation for this class was generated from the following file:


- [l4/cxx/exceptions](#)

## 15.234 L4::Vcon Class Reference

C++ [L4 Vcon](#) interface, see [Virtual Console](#) for the C interface.


```
#include <vcon>
```

Inheritance diagram for L4::Vcon:





Collaboration diagram for L4::Vcon:



## Public Member Functions

- `l4_msgtag_t send` (char const \*buf, unsigned size, `l4_utcb_t *utcb=l4_utcb()`) const noexcept  
Send data to *this* virtual console.
- `long write` (char const \*buf, unsigned size, `l4_utcb_t *utcb=l4_utcb()`) const noexcept  
Write data to *this* virtual console.
- `int read` (char \*buf, unsigned size, `l4_utcb_t *utcb=l4_utcb()`) const noexcept

- *Read data from `this` virtual console.*
- `int read_with_flags (char *buf, unsigned size, l4\_utcb\_t *utcb=l4\_utcb\(\)) const noexcept`  
*Read data from `this` virtual console which also returns flags.*
- `l4\_msgtag\_t set_attr (l4\_vcon\_attr\_t const *attr, l4\_utcb\_t *utcb=l4\_utcb\(\)) const noexcept`  
*Set the attributes of `this` virtual console.*
- `l4\_msgtag\_t get_attr (l4\_vcon\_attr\_t *attr, l4\_utcb\_t *utcb=l4\_utcb\(\)) const noexcept`  
*Get attributes of `this` virtual console.*

## Public Member Functions inherited from [L4::Icu](#)

- `l4\_msgtag\_t bind (unsigned irqnum, L4::Cap< Triggerable > irq, l4\_utcb\_t *utcb=l4\_utcb\(\)) noexcept`  
*Bind an interrupt line of an interrupt controller to an interrupt object.*
- `l4\_msgtag\_t unbind (unsigned irqnum, L4::Cap< Triggerable > irq, l4\_utcb\_t *utcb=l4\_utcb\(\)) noexcept`  
*Remove binding of an interrupt line from the interrupt controller object.*
- `l4\_msgtag\_t info (l4\_icu\_info\_t *info, l4\_utcb\_t *utcb=l4\_utcb\(\)) noexcept`  
*Get information about the ICU features.*
- `l4\_msgtag\_t msi_info (l4\_umword\_t irqnum, l4\_uint64\_t source, l4\_icu\_msi\_info\_t *msi_info)`  
*Get MSI info about IRQ.*
- `l4\_msgtag\_t mask (unsigned irqnum, l4\_umword\_t *label=0, l4\_timeout\_t to=L4\_IPC\_NEVER, l4\_utcb\_t *utcb=l4\_utcb\(\)) noexcept`  
*Mask an IRQ line.*
- `l4\_msgtag\_t set_mode (unsigned irqnum, l4\_umword\_t mode, l4\_utcb\_t *utcb=l4\_utcb\(\)) noexcept`  
*Set interrupt mode.*

## Public Member Functions inherited from [L4::Irq\\_eoi](#)

- `l4\_msgtag\_t unmask (unsigned irqnum, l4\_umword\_t *label=0, l4\_timeout\_t to=L4\_IPC\_NEVER, l4\_utcb\_t *utcb=l4\_utcb\(\)) noexcept`  
*Unmask the given interrupt line.*

## Additional Inherited Members

## Protected Types inherited from [L4::Kobject\\_t](#)< [Vcon](#), [Icu](#), [L4\\_PROTO\\_LOG](#) >

- `typedef Vcon Class`  
*The target interface type (inheriting from [Kobject\\_t](#)).*
- `typedef Typeid::Iface< PROTO, Vcon > __Iface`  
*The interface description for the derived class.*
- `typedef Typeid::Merge_list< Typeid::Iface_list< __Iface >, typename Icu::__Iface_list > __Iface_list`  
*The list of all RPC interfaces provided directly or through inheritance.*

## Protected Types inherited from

## [L4::Kobject\\_t](#)< [Icu](#), [Irq\\_eoi](#), [L4\\_PROTO\\_IRQ](#), [Type\\_info::Demand\\_t](#)< 1 > >

- `typedef Icu Class`  
*The target interface type (inheriting from [Kobject\\_t](#)).*
- `typedef Typeid::Iface< PROTO, Icu > __Iface`  
*The interface description for the derived class.*
- `typedef Typeid::Merge_list< Typeid::Iface_list< __Iface >, typename Irq\_eoi::__Iface_list > __Iface_list`  
*The list of all RPC interfaces provided directly or through inheritance.*

### Protected Member Functions inherited from [L4::Kobject\\_t< Vcon, Icu, L4\\_PROTO\\_LOG >](#)

- [L4::Cap< Class > c \(\)](#) const noexcept  
*Get the capability to ourselves.*

### Protected Member Functions inherited from [L4::Kobject\\_t< Icu, Irq\\_eoi, L4\\_PROTO\\_IRQ, Type\\_info::Demand\\_t< 1 > >](#)

- [L4::Cap< Class > c \(\)](#) const noexcept  
*Get the capability to ourselves.*

### Static Protected Member Functions inherited from [L4::Kobject\\_t< Vcon, Icu, L4\\_PROTO\\_LOG >](#)

- static void [\\_\\_check\\_protocols\\_\\_ \(\)](#) noexcept  
*Helper to check for protocol conflicts.*

### Static Protected Member Functions inherited from [L4::Kobject\\_t< Icu, Irq\\_eoi, L4\\_PROTO\\_IRQ, Type\\_info::Demand\\_t< 1 > >](#)

- static void [\\_\\_check\\_protocols\\_\\_ \(\)](#) noexcept  
*Helper to check for protocol conflicts.*

## 15.234.1 Detailed Description

C++ [L4 Vcon](#) interface, see [Virtual Console](#) for the C interface.

[L4::Vcon](#) is a virtual console for simple character-based input and output. The interrupt for read events is provided by the virtual key interrupt.

The [Vcon](#) interface inherits from [L4::Icu](#) and [L4::Irq\\_eoi](#) for managing the virtual key interrupt which, in contrast to hardware IRQs, implements a limited functionality:

- Only IRQ line 0 is supported, no MSI vectors.
- The IRQ is edge-triggered and the IRQ mode cannot be changed.
- As the IRQ is edge-triggered, it does not have to be explicitly unmasked.

A server implementing the virtual console protocol has a queue for input events. When the first input event is added to the empty queue, the virtual key interrupt is triggered. Further events are added to the queue without generating further interrupts. The queue is emptied when a client reads all queued input events.

#### Include File

```
#include <l4/sys/vcon>
```

See the [Virtual Console](#) for the C interface.

Definition at line 45 of file [vcon](#).

## 15.234.2 Member Function Documentation

### 15.234.2.1 get\_attr()

```
l4_msgtag_t L4::Vcon::get_attr (
    l4_vcon_attr_t * attr,
    l4_utcb_t * utcb = l4_utcb()) const [inline], [noexcept]
```

Get attributes of this virtual console.

#### Parameters

out	<i>attr</i>	Attribute structure. Contains the attributes after a successful call of this function.
	<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. Defaults to <a href="#">l4_utcb</a> .


#### Returns

Syscall return tag.

Definition at line 151 of file [vcon](#).

References [L4::Kobject::cap\(\)](#), and [l4\\_vcon\\_get\\_attr\\_u\(\)](#).

Here is the call graph for this function:



### 15.234.2.2 read()

```
int L4::Vcon::read (
    char * buf,
    unsigned size,
    l4_utcb_t * utcb = l4_utcb()) const [inline], [noexcept]
```

Read data from this virtual console.

#### Parameters

out	<i>buf</i>	Pointer to data buffer.
	<i>size</i>	Size of the data buffer in bytes.

	<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. Defaults to <a href="#">l4_utcb</a> .
--	-------------	--

**Return values**

<code>-L4_EPERM</code>	Insufficient permissions; see precondition.
<code>&gt;size</code>	More bytes to read, <code>size</code> bytes are in the buffer <code>buf</code> .
<code>&lt;=size</code>	Number of bytes read.

**Precondition**

The invoked [Vcon](#) capability must have the permission [L4\\_CAP\\_FPAGE\\_W](#).


**Note**

Size must not exceed [L4\\_VCON\\_READ\\_SIZE](#).

Definition at line 98 of file [vcon](#).

References [L4::Kobject::cap\(\)](#), and [l4\\_vcon\\_read\\_u\(\)](#).

Here is the call graph for this function:

**15.234.2.3 read\_with\_flags()**

```

int L4::Vcon::read_with_flags (
    char * buf,
    unsigned size,
    l4\_utcb\_t * utcb = l4\_utcb()) const [inline], [noexcept]

```

Read data from `this` virtual console which also returns flags.

**Parameters**

out	<i>buf</i>	Pointer to data buffer.
-----	------------	-------------------------

	<i>size</i>	Size of the data buffer in bytes.
	<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. Defaults to <a href="#">l4_utcb</a> .

### Return values

<code>-L4_EPERM</code>	Insufficient permissions; see precondition.
<code>&gt;size</code>	More bytes to read, <i>size</i> bytes are in the buffer <i>buf</i> .
<code>&lt;=size</code>	Number of bytes read.

### Precondition

The invoked [Vcon](#) capability must have the permission [L4\\_CAP\\_FPAGE\\_W](#).

If this function returns a positive value the caller can check the [L4\\_VCON\\_READ\\_STAT\\_BREAK](#) flag bit for a break condition. The bytes read can be obtained by masking the return value with [L4\\_VCON\\_READ\\_SIZE\\_MASK](#).

If a break condition is signaled, it is always the first event in the transmitted content, i.e. all characters supplied by this read call follow the break condition.


### Note

Size must not exceed [L4\\_VCON\\_READ\\_SIZE](#).

Definition at line [125](#) of file [vcon](#).

References [L4::Kobject::cap\(\)](#).

Here is the call graph for this function:



### 15.234.2.4 send()

```

14_msgtag_t L4::Vcon::send (
    char const * buf,
    unsigned size,
    14_utcb_t * utcb = 14_utcb()) const [inline], [noexcept]
  
```

Send data to this virtual console.

**Parameters**

<i>buf</i>	Pointer to the data buffer.
<i>size</i>	Size of the data buffer in bytes.
<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. Defaults to <a href="#">l4_utcb</a> .

**Returns**

Syscall return tag


**Note**

Size must not exceed [L4\\_VCON\\_WRITE\\_SIZE](#), a proper value of the `size` parameter is NOT checked. Also, this function is a send only operation, this means there is no return value except for a failed send operation. Use [l4\\_ipc\\_error\(\)](#) to check for send errors, do not use [l4\\_error\(\)](#), as [l4\\_error\(\)](#) will always return an error.

Definition at line 65 of file [vcon](#).

References [L4::Kobject::cap\(\)](#), and [l4\\_vcon\\_send\\_u\(\)](#).

Here is the call graph for this function:

**15.234.2.5 set\_attr()**

```

l4_msgtag_t L4::Vcon::set_attr (
    l4_vcon_attr_t const * attr,
    l4_utcb_t * utcb = l4_utcb()) const [inline], [noexcept]

```

Set the attributes of `this` virtual console.

**Parameters**

<i>attr</i>	Attribute structure with the attributes for the virtual console.
<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. Defaults to <a href="#">l4_utcb</a> .


**Returns**

Syscall return tag.

Definition at line 138 of file [vcon](#).

References [L4::Kobject::cap\(\)](#), and [l4\\_vcon\\_set\\_attr\\_u\(\)](#).

Here is the call graph for this function:

**15.234.2.6 write()**

```

long L4::Vcon::write (
    char const * buf,
    unsigned size,
    l4_utcb_t * utcb = l4_utcb()) const [inline], [noexcept]

```

Write data to this virtual console.

**Parameters**

<i>buf</i>	Pointer to the data buffer.
<i>size</i>	Size of the data buffer in bytes.
<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. Defaults to <a href="#">l4_utcb</a> .

**Return values**


<i>&lt;0</i>	Error.
<i>&gt;=0</i>	Number of bytes written to the virtual console.

Definition at line 79 of file [vcon](#).

References [L4::Kobject::cap\(\)](#), and [l4\\_vcon\\_write\\_u\(\)](#).



Here is the call graph for this function:



The documentation for this class was generated from the following file:


- [l4/sys/vcon](#)

## 15.235 L4::Vm Class Reference


Virtual machine host address space.

```
#include <vm>
```

Inheritance diagram for L4::Vm:



Collaboration diagram for L4::Vm:



### Additional Inherited Members

## Public Member Functions inherited from L4::Task

- `l4_msgtag_t map (Cap< Task > const &src_task, l4_fpage_t const &snd_fpage, l4_umword_t snd_base, l4_utcb_t *utcb=l4_utcb()) noexcept`

- *Map resources available in the source task to a destination task.*  
**`l4_msgtag_t unmap`** (`l4_fpage_t` const &fpage, `l4_umword_t` map\_mask, `l4_utcb_t` \*utcb=`l4_utcb()`) noexcept  
*Revoke rights from the task.*
- **`l4_msgtag_t unmap_batch`** (`l4_fpage_t` const \*fpages, unsigned num\_fpages, `l4_umword_t` map\_mask, `l4_utcb_t` \*utcb=`l4_utcb()`) noexcept  
*Revoke rights from a task.*
- **`l4_msgtag_t delete_obj`** (`L4::Cap`< void > obj, `l4_utcb_t` \*utcb=`l4_utcb()`) noexcept  
*Release capability and delete object.*
- **`l4_msgtag_t release_cap`** (`L4::Cap`< void > cap, `l4_utcb_t` \*utcb=`l4_utcb()`) noexcept  
*Release object capability.*
- **`l4_msgtag_t cap_valid`** (`Cap`< void > const &cap, `l4_utcb_t` \*utcb=`l4_utcb()`) noexcept  
*Check whether a capability is present (refers to an object).*
- **`l4_msgtag_t cap_equal`** (`Cap`< void > const &cap\_a, `Cap`< void > const &cap\_b, `l4_utcb_t` \*utcb=`l4_utcb()`) noexcept  
*Test whether two capabilities point to the same object with the same permissions (only considering selected permissions).*
- **`l4_msgtag_t add_ku_mem`** (`l4_fpage_t` \*fpage, `l4_utcb_t` \*utcb=`l4_utcb()`) noexcept  
*Add kernel-user memory.*

## Public Member Functions inherited from `L4::Kobject`

- **`l4_msgtag_t dec_refcnt`** (`l4_mword_t` diff, `l4_utcb_t` \*utcb=`l4_utcb()`)  
*Decrement the in kernel reference counter for the object.*

## Protected Types inherited from `L4::Kobject_t`< `Vm`, `Task`, `L4_PROTO_VM` >

- typedef `Vm` **Class**  
*The target interface type (inheriting from `Kobject_t`).*
- typedef `Typeid::Iface`< `PROTO`, `Vm` > **\_\_Iface**  
*The interface description for the derived class.*
- typedef `Typeid::Merge_list`< `Typeid::Iface_list`< **\_\_Iface** >, typename `Task::__Iface_list` > **\_\_Iface\_list**  
*The list of all RPC interfaces provided directly or through inheritance.*

## Protected Types inherited from `L4::Kobject_t`< `Task`, `Kobject`, `L4_PROTO_TASK`, `Type_info::Demand_t`< 2 > >

- typedef `Task` **Class**  
*The target interface type (inheriting from `Kobject_t`).*
- typedef `Typeid::Iface`< `PROTO`, `Task` > **\_\_Iface**  
*The interface description for the derived class.*
- typedef `Typeid::Merge_list`< `Typeid::Iface_list`< **\_\_Iface** >, typename `Kobject::__Iface_list` > **\_\_Iface\_list**  
*The list of all RPC interfaces provided directly or through inheritance.*

## Protected Member Functions inherited from `L4::Kobject_t`< `Vm`, `Task`, `L4_PROTO_VM` >

- **`L4::Cap`**< `Class` > **`c`** () const noexcept  
*Get the capability to ourselves.*

**Protected Member Functions inherited from****L4::Kobject\_t< Task, Kobject, L4\_PROTO\_TASK, Type\_info::Demand\_t< 2 > >**

- **L4::Cap< Class > c ()** const noexcept  
*Get the capability to ourselves.*

**Protected Member Functions inherited from L4::Kobject**

- **l4\_cap\_idx\_t cap ()** const noexcept  
*Return capability selector.*

**Static Protected Member Functions inherited from****L4::Kobject\_t< Vm, Task, L4\_PROTO\_VM >**

- static void **\_\_check\_protocols\_\_ ()** noexcept  
*Helper to check for protocol conflicts.*

**Static Protected Member Functions inherited from****L4::Kobject\_t< Task, Kobject, L4\_PROTO\_TASK, Type\_info::Demand\_t< 2 > >**

- static void **\_\_check\_protocols\_\_ ()** noexcept  
*Helper to check for protocol conflicts.*

**15.235.1 Detailed Description**

Virtual machine host address space.

[L4::Vm](#) is a specialisation of [L4::Task](#), used for virtual machines. The microkernel employs an appropriate page-table format for hosting VMs, such as ePT on VT-x. On Arm, it offers a call to make the virtual GICC area available to the VM.

Definition at line 30 of file [vm](#).

The documentation for this class was generated from the following file:


- [l4/sys/vm](#)

**15.236 l4\_buf\_regs\_t Struct Reference**

Encapsulation of the buffer-registers block in the UTCB.

```
#include <utcb.h>
```

Collaboration diagram for [l4\\_buf\\_regs\\_t](#):



## Data Fields

- [l4\\_umword\\_t](#) **bdr**  
*Buffer descriptor.*
- [l4\\_umword\\_t](#) **br** [L4\_UTCB\_GENERIC\_BUFFERS\_SIZE]  
*Buffer registers.*

### 15.236.1 Detailed Description

Encapsulation of the buffer-registers block in the UTCB.

Definition at line 147 of file [utcb.h](#).

The documentation for this struct was generated from the following file:

- [l4/sys/utcb.h](#)

### 15.237 l4\_exc\_regs\_t Struct Reference

UTCB structure for exceptions.

```
#include <utcb.h>
```

Collaboration diagram for `l4_exc_regs_t`:

l4_exc_regs_t
+ pfa
+ err
+ r
+ sp
+ ulr
+ _dummy1
+ pc
+ cpsr
+ tpidrro
+ tpidrurw
and 31 more...

## Data Fields

- [l4\\_umword\\_t pfa](#)  
*page fault address*
- [l4\\_umword\\_t err](#)  
*error code*
- [l4\\_umword\\_t r \[13\]](#)  
*registers*
- [l4\\_umword\\_t sp](#)  
*stack pointer*
- [l4\\_umword\\_t ulr](#)  
*ulr*
- [l4\\_umword\\_t \\_dummy1](#)  
*dummy*
- [l4\\_umword\\_t pc](#)  
*pc*
- [l4\\_umword\\_t cpsr](#)  
*cpsr*
- [l4\\_umword\\_t tpidruro](#)  
*Thread-ID register.*
- [l4\\_umword\\_t tpidrurw](#)  
*Thread-ID register.*
- [l4\\_umword\\_t r15](#)  
*r15*
- [l4\\_umword\\_t r14](#)  
*r14*
- [l4\\_umword\\_t r13](#)  
*r13*
- [l4\\_umword\\_t r12](#)  
*r12*
- [l4\\_umword\\_t r11](#)  
*r11*
- [l4\\_umword\\_t r10](#)  
*r10*
- [l4\\_umword\\_t r9](#)  
*r9*
- [l4\\_umword\\_t r8](#)  
*r8*
- [l4\\_umword\\_t rdi](#)  
*rdi*
- [l4\\_umword\\_t rsi](#)  
*rsi*
- [l4\\_umword\\_t rbp](#)  
*rbp*
- [l4\\_umword\\_t rbx](#)  
*rbx*
- [l4\\_umword\\_t rdx](#)  
*rdx*
- [l4\\_umword\\_t rcx](#)  
*rcx*
- [l4\\_umword\\_t rax](#)

- rax*
- [l4\\_umword\\_t trapno](#)  
*trap number*
- [l4\\_umword\\_t dummy1](#)  
*dummy*
- [l4\\_umword\\_t ss](#)  
*stack segment register*
- [l4\\_umword\\_t es](#)  
*es register*
- [l4\\_umword\\_t ds](#)  
*ds register*
- [l4\\_umword\\_t gs](#)  
*gs register*
- [l4\\_umword\\_t fs](#)  
*fs register*
- [l4\\_umword\\_t edi](#)  
*edi register*
- [l4\\_umword\\_t esi](#)  
*esi register*
- [l4\\_umword\\_t ebp](#)  
*ebp register*
- [l4\\_umword\\_t ebx](#)  
*ebx register*
- [l4\\_umword\\_t edx](#)  
*edx register*
- [l4\\_umword\\_t ecx](#)  
*ecx register*
- [l4\\_umword\\_t eax](#)  
*eax register*

### 15.237.1 Detailed Description

UTCB structure for exceptions.

#### Examples

[examples/sys/aliens/main.c](#), [examples/sys/singlestep/main.c](#), and [examples/sys/start-with-exc/main.c](#).

Definition at line 27 of file [utcb.h](#).

### 15.237.2 Field Documentation

#### 15.237.2.1 flags

[l4\\_umword\\_t](#) [l4\\_exc\\_regs\\_t::flags](#)

rflags

eflags

Definition at line 37 of file [utcb.h](#).



**15.237.2.2 ss**

`l4_umword_t l4_exc_regs_t::ss`

stack segment register

ss register

Definition at line 64 of file [utcb.h](#).

The documentation for this struct was generated from the following files:


- [arm/l4/sys/arch/utcb.h](#)
- [arm64/l4/sys/arch/utcb.h](#)
- [amd64/l4/sys/arch/utcb.h](#)
- [x86/l4/sys/arch/utcb.h](#)

**15.238 l4\_fpage\_t Union Reference**

[L4](#) flexpage type.

```
#include <__l4_fpage.h>
```

Collaboration diagram for `l4_fpage_t`:

**Data Fields**

- [l4\\_umword\\_t](#) **fpage**  
*Raw value.*
- [l4\\_umword\\_t](#) **raw**  
*Raw value.*

**15.238.1 Detailed Description**

[L4](#) flexpage type.

Definition at line 76 of file [\\_\\_l4\\_fpage.h](#).

The documentation for this union was generated from the following file:


- [l4/sys/\\_\\_l4\\_fpage.h](#)

## 15.239 l4\_icu\_info\_t Struct Reference


Info structure for an ICU.

```
#include <icu.h>
```

Inheritance diagram for l4\_icu\_info\_t:



Collaboration diagram for l4\_icu\_info\_t:



### Data Fields

- unsigned `features`  
*Feature flags.*
- unsigned `nr_irqs`  
*The number of IRQ lines supported by the ICU,.*
- unsigned `nr_msis`  
*The number of MSI vectors supported by the ICU,.*

### 15.239.1 Detailed Description

Info structure for an ICU.

This structure contains information about the features of an ICU.

See also

[l4\\_icu\\_info\(\)](#).

Definition at line 163 of file [icu.h](#).

### 15.239.2 Field Documentation

#### 15.239.2.1 features

```
unsigned l4_icu_info_t::features
```

Feature flags.

If [L4\\_ICU\\_FLAG\\_MSI](#) is set the ICU supports MSIs.

Definition at line 170 of file [icu.h](#).

Referenced by [L4::Icu::Info::supports\\_msi\(\)](#).

The documentation for this struct was generated from the following file:


- [l4/sys/icu.h](#)

## 15.240 l4\_icu\_msi\_info\_t Struct Reference

Info to use for a specific MSI.

```
#include <icu.h>
```

Collaboration diagram for `l4_icu_msi_info_t`:



## Data Fields

- [l4\\_uint64\\_t](#) **msi\_addr**  
*Value to use as address when sending this MSI.*
- [l4\\_uint32\\_t](#) **msi\_data**  
*Value to use as data written to msi\_addr, when sending this MSI.*

### 15.240.1 Detailed Description

Info to use for a specific MSI.

Definition at line [184](#) of file [icu.h](#).

The documentation for this struct was generated from the following file:


- [l4/sys/icu.h](#)

## 15.241 l4\_kernel\_info\_mem\_desc\_t Struct Reference

Memory descriptor data structure.

```
#include <memdesc.h>
```

Collaboration diagram for `l4_kernel_info_mem_desc_t`:



### 15.241.1 Detailed Description

Memory descriptor data structure.

#### Note

This data type is opaque, and must be accessed by the accessor functions defined in this module.

Definition at line [77](#) of file [memdesc.h](#).

The documentation for this struct was generated from the following file:


- [l4/sys/memdesc.h](#)

## 15.242 l4\_kernel\_info\_t Struct Reference

[L4 Kernel Interface Page](#).

```
#include <kip.h>
```

Collaboration diagram for l4\_kernel\_info\_t:



### Data Fields

- [l4\\_uint32\\_t](#) **magic**  
*Kernel Info Page identifier ("L4μK").*
- [l4\\_uint32\\_t](#) **version**  
*Kernel version.*
- [l4\\_uint8\\_t](#) **offset\_version\_strings**  
*offset to version string*
- [l4\\_uint8\\_t](#) **\_fill0** [3]  
*reserved*
- [l4\\_uint8\\_t](#) **kip\_sys\_calls**  
*pointer to system calls*
- [l4\\_uint8\\_t](#) **\_fill1** [2]  
*reserved*
- [l4\\_uint64\\_t](#) **sigma0\_ip**  
*Sigma0 instruction pointer.*
- [l4\\_uint64\\_t](#) **root\_ip**  
*Root task instruction pointer.*
- [l4\\_uint64\\_t](#) **frequency\_cpu**

- CPU frequency in kHz.*
- [l4\\_uint64\\_t](#) **acpi\_rsdp\_addr**  
*ACPI RSDP/XSDP.*
- [l4\\_uint64\\_t](#) **dt\_addr**  
*Device Tree.*
- [l4\\_uint64\\_t](#) **user\_ptr**  
*user\_ptr*
- [l4\\_uint32\\_t](#) **scheduler\_granularity**  
*for rounding time slices*
- [l4\\_uint32\\_t](#) **mem\_descs**  
*memory descriptors relative to Kip*
- [l4\\_uint32\\_t](#) **mem\_descs\_num**  
*number of memory descriptors*
- [l4\\_uint64\\_t](#) **\_res2** [2]  
*internal - spare space*

### 15.242.1 Detailed Description

[L4 Kernel Interface Page.](#)

32-bit architecture may assume that the upper 32 bits of addresses is 0

Definition at line 36 of file [kip.h](#).

The documentation for this struct was generated from the following file:


- [l4/sys/kip.h](#)

## 15.243 l4\_msg\_regs\_t Union Reference

Encapsulation of the message-register block in the UTCB.

```
#include <utcb.h>
```

Collaboration diagram for `l4_msg_regs_t`:



**Data Fields**

- [l4\\_umword\\_t](#) **mr** [L4\_UTCB\_GENERIC\_DATA\_SIZE]  
*Message registers.*
- [l4\\_uint64\\_t](#) **mr64** [L4\_UTCB\_GENERIC\_DATA\_SIZE/(sizeof([l4\\_uint64\\_t](#))/sizeof([l4\\_umword\\_t](#)))]  
*Message registers 64bit alias.*

**15.243.1 Detailed Description**

Encapsulation of the message-register block in the UTCB.

**Examples**

[examples/sys/utcb-ipc/main.c](#).

Definition at line 132 of file [utcb.h](#).

The documentation for this union was generated from the following file:

- l4/sys/[utcb.h](#)

**15.244 l4\_msgtag\_t Struct Reference**

Message tag data structure.

```
#include <types.h>
```

Collaboration diagram for l4\_msgtag\_t:

l4_msgtag_t
+ raw
+ label()
+ label()
+ words()
+ items()
+ flags()
+ is_page_fault()
+ is_exception()
+ is_sigma0()
+ is_io_page_fault()
+ has_error()

## Public Member Functions

- long **label** () const [L4\\_NOTHROW](#)  
*Get the protocol value.*
- void **label** (long v) [L4\\_NOTHROW](#)  
*Set the protocol value.*
- unsigned **words** () const [L4\\_NOTHROW](#)  
*Get the number of untyped words.*
- unsigned **items** () const [L4\\_NOTHROW](#)  
*Get the number of typed items.*
- unsigned **flags** () const [L4\\_NOTHROW](#)  
*Get the flags value.*
- bool **is\_page\_fault** () const [L4\\_NOTHROW](#)  
*Test if protocol indicates page-fault protocol.*
- bool **is\_exception** () const [L4\\_NOTHROW](#)  
*Test if protocol indicates exception protocol.*
- bool **is\_sigma0** () const [L4\\_NOTHROW](#)  
*Test if protocol indicates sigma0 protocol.*
- bool **is\_io\_page\_fault** () const [L4\\_NOTHROW](#)  
*Test if protocol indicates IO-page-fault protocol.*
- bool **has\_error** () const [L4\\_NOTHROW](#)  
*Test if flags indicate an error.*

## Data Fields

- [l4\\_mword\\_t](#) **raw**  
*raw value*

### 15.244.1 Detailed Description

Message tag data structure.

#### Include File

```
#include <l4/sys/types.h>
```

Describes the details of an IPC operation, in particular which parts of the UTCB have to be transmitted, and also flags to enable real-time and FPU extensions.

The message tag also contains a user-defined label that could be used to specify a protocol ID. Some negative values are reserved for kernel protocols such as page faults and exceptions.

The type must be treated completely opaque.

#### Examples

[examples/libs/l4re/c++/shared\\_ds/ds\\_srv.cc](#), [examples/libs/l4re/streammap/server.cc](#), [examples/sys/aliens/main.c](#), [examples/sys/ipc/ipc\\_example.c](#), [examples/sys/singlestep/main.c](#), [examples/sys/start-with-exc/main.c](#), and [examples/sys/utcb-ipc/main.c](#).

Definition at line 265 of file [types.h](#).



## 15.244.2 Member Function Documentation

### 15.244.2.1 flags()

```
unsigned l4_msgtag_t::flags () const [inline]
```

Get the flags value.

The flags are a combination of the flags defined by [L4\\_msgtag\\_flags](#).

Definition at line 283 of file [types.h](#).

References [l4\\_msgtag\\_flags\(\)](#), and [L4\\_NOTHROW](#).

Here is the call graph for this function:



### 15.244.2.2 has\_error()

```
bool l4_msgtag_t::has_error () const [inline]
```

Test if flags indicate an error.

If true, the error code is stored in the UTCB, see [l4\\_utcb\\_tcr\(\)->error](#).

Definition at line 299 of file [types.h](#).


References [l4\\_msgtag\\_has\\_error\(\)](#), and [L4\\_NOTHROW](#).

Referenced by [L4Re::chkipc\(\)](#), [L4Re::chksys\(\)](#), [L4::Server< LOOP\\_HOOKS >::internal\\_loop\(\)](#), [L4::Server< LOOP\\_HOOKS >::reply](#) and [L4::throw\\_ipc\\_exception\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



The documentation for this struct was generated from the following file:


- [l4/sys/types.h](#)

## 15.245 l4\_sched\_cpu\_set\_t Struct Reference

CPU sets.

```
#include <scheduler.h>
```

Collaboration diagram for l4\_sched\_cpu\_set\_t:



### Public Member Functions

- unsigned char [granularity](#) () const
- unsigned [offset](#) () const
- void [set](#) (unsigned char [granularity](#), unsigned [offset](#))  
*Set offset and granularity.*

## Data Fields

- [l4\\_umword\\_t gran\\_offset](#)  
*Combination of granularity and offset.*
- [l4\\_umword\\_t map](#)  
*Bitmap of CPUs.*

## 15.245.1 Detailed Description

CPU sets.

### Examples

[examples/sys/migrate/thread\\_migrate.cc](#).

Definition at line 58 of file [scheduler.h](#).

## 15.245.2 Member Function Documentation

### 15.245.2.1 granularity()

```
unsigned char l4_sched_cpu_set_t::granularity () const [inline]
```

#### Returns


Get granularity value

Definition at line 81 of file [scheduler.h](#).

References [gran\\_offset](#).

Referenced by [set\(\)](#).

Here is the caller graph for this function:



### 15.245.2.2 `offset()`

```
unsigned l4_sched_cpu_set_t::offset () const [inline]
```

#### Returns

Get offset value

Definition at line 83 of file [scheduler.h](#).

References [gran\\_offset](#).

Referenced by [set\(\)](#).

Here is the caller graph for this function:



### 15.245.2.3 `set()`

```
void l4_sched_cpu_set_t::set (  
    unsigned char granularity,  
    unsigned offset) [inline]
```

Set offset and granularity.


#### Parameters

<i>granularity</i>	Granularity in log2 notation.
<i>offset</i>	Offset. Must be a multiple of $2^{\text{granularity}}$ .

Definition at line 90 of file [scheduler.h](#).

References [gran\\_offset](#), [granularity\(\)](#), and [offset\(\)](#).

Here is the call graph for this function:



### 15.245.3 Field Documentation

#### 15.245.3.1 gran\_offset

`l4_umword_t l4_sched_cpu_set_t::gran_offset`

Combination of granularity and offset.

The granularity defines how many CPUs each bit in map describes. And the offset is the number of the first CPU described by the first bit in the bitmap.

##### Precondition

offset must be a multiple of  $2^{\text{granularity}}$ .

MSB	LSB
8bit granularity	24bit offset ..

Definition at line 72 of file [scheduler.h](#).

Referenced by [granularity\(\)](#), [L4::Scheduler::info\(\)](#), [l4\\_sched\\_cpu\\_set\(\)](#), [offset\(\)](#), and [set\(\)](#).

The documentation for this struct was generated from the following file:


- [l4/sys/scheduler.h](#)

## 15.246 l4\_sched\_param\_t Struct Reference

Scheduler parameter set.

```
#include <scheduler.h>
```

Collaboration diagram for l4\_sched\_param\_t:



### Data Fields

- [l4\\_sched\\_cpu\\_set\\_t](#) **affinity**  
*CPU affinity.*
- [l4\\_umword\\_t](#) **prio**  
*Priority for scheduling.*
- [l4\\_umword\\_t](#) **quantum**  
*Timeslice in micro seconds.*

### 15.246.1 Detailed Description

Scheduler parameter set.

#### Examples

[examples/sys/aliens/main.c](#), [examples/sys/migrate/thread\\_migrate.cc](#), [examples/sys/singlestep/main.c](#), [examples/sys/start-with-exc/main.c](#), and [examples/sys/utcb-ipc/main.c](#).

Definition at line 173 of file [scheduler.h](#).

## 15.246.2 Field Documentation

### 15.246.2.1 prio

```
l4_umword_t l4_sched_param_t::prio
```

Priority for scheduling.

The kernel supports priorities for userland threads in the range of 1..255. Priority 0 is reserved for the kernel.

Definition at line 182 of file [scheduler.h](#).

Referenced by [l4\\_sched\\_param\(\)](#).

The documentation for this struct was generated from the following file:


- [l4/sys/scheduler.h](#)

## 15.247 l4\_snd\_fpage\_t Struct Reference

Send-flexpage types.

```
#include <__l4_fpage.h>
```

Collaboration diagram for l4\_snd\_fpage\_t:



### Data Fields

- [l4\\_umword\\_t](#) **snd\_base**  
*Offset in receive window (send base).*
- [l4\\_fpage\\_t](#) **fpage**  
*Source flexpage descriptor.*

### 15.247.1 Detailed Description

Send-flexpage types.

Definition at line 99 of file [\\_\\_l4\\_fpage.h](#).

The documentation for this struct was generated from the following file:


- [l4/sys/\\_\\_l4\\_fpage.h](#)

## 15.248 l4\_thread\_regs\_t Struct Reference

Encapsulation of the thread-control-register block of the UTCB.

```
#include <utcb.h>
```

Collaboration diagram for l4\_thread\_regs\_t:



### Data Fields

- [l4\\_umword\\_t](#) `error`  
*System call error code (see [l4\\_ipc\\_tcr\\_error\\_t](#)).*
- [l4\\_umword\\_t](#) `free_marker`  
*Kernel free marker.*
- [l4\\_umword\\_t](#) `user` [3]  
*User values (ignored and preserved by the kernel).*

### 15.248.1 Detailed Description

Encapsulation of the thread-control-register block of the UTCB.

Definition at line 164 of file [utcb.h](#).



## 15.248.2 Field Documentation

### 15.248.2.1 error

`l4_umword_t l4_thread_regs_t::error`

System call error code (see [l4\\_ipc\\_tcr\\_error\\_t](#)).

If the kernel indicates an error in the message tag (see [l4\\_msgtag\\_has\\_error\(\)](#) and [l4\\_msgtag\\_t::has\\_error\(\)](#)), the kernel writes the error code to this field.

Definition at line 171 of file [utcb.h](#).

### 15.248.2.2 free\_marker

`l4_umword_t l4_thread_regs_t::free_marker`

Kernel free marker.

The kernel sets this field to zero as soon as it is guaranteed that the kernel does not use the UTCB anymore for the bound thread. This usually happens while a thread is deleted. However, it is not defined when exactly the kernel sets the field. In particular, the point in time is not necessarily related to any IPC.

Userland may use this field for determining if a UTCB can be re-used for another thread. Note that, in order to make use of that feature, userland has to set this field to a non-zero value when a thread is bound with this UTCB.

Definition at line 185 of file [utcb.h](#).

The documentation for this struct was generated from the following file:


- [l4/sys/utcb.h](#)

## 15.249 l4\_timeout\_s Struct Reference

Basic timeout specification.

```
#include <__timeout.h>
```

Collaboration diagram for `l4_timeout_s`:



## Data Fields

- [l4\\_uint16\\_t](#) *timeout value*

### 15.249.1 Detailed Description

Basic timeout specification.

If bit 15 == 0, basically a floating point number with 10 bits mantissa and 5 bits exponent ( $t = m \cdot 2^e$ ).

If the mantissa is zero, the exponent encodes special values, see [L4\\_IPC\\_TIMEOUT\\_0](#) and [L4\\_IPC\\_TIMEOUT\\_NEVER](#).

If bit 15 == 1 the timeout is absolute and the lower 6 bits encode the index of the UTCB buffer register(s) holding the absolute 64-bit timeout value. On 32-bit systems, two consecutive UTCB buffer registers are used.

Definition at line 40 of file [\\_\\_timeout.h](#).

The documentation for this struct was generated from the following file:


- [l4/sys/\\_\\_timeout.h](#)

## 15.250 l4\_timeout\_t Union Reference

Timeout pair.

```
#include <__timeout.h>
```

Collaboration diagram for `l4_timeout_t`:



## Data Fields

- [l4\\_uint32\\_t](#) **raw**  
*raw value*
- struct {
  - [l4\\_timeout\\_s](#) **rcv**  
*receive timeout*
  - [l4\\_timeout\\_s](#) **snd**  
*send timeout*
- **p**  
*combined timeout*

### 15.250.1 Detailed Description

Timeout pair.

For IPC there are usually a send and a receive timeout. So this structure contains a pair of timeouts.

Definition at line 52 of file [\\_\\_timeout.h](#).

The documentation for this union was generated from the following file:

- l4/sys/\_\_timeout.h

## 15.251 l4\_vcon\_attr\_t Struct Reference

Vcon attribute structure.

```
#include <vcon.h>
```

Collaboration diagram for l4\_vcon\_attr\_t:

l4_vcon_attr_t
+ i_flags
+ o_flags
+ l_flags
+ set_raw()

## Public Member Functions

- void [set\\_raw](#) ()  
*Set terminal attributes to disable all special processing.*

## Data Fields

- [l4\\_umword\\_t i\\_flags](#)  
*input flags*
- [l4\\_umword\\_t o\\_flags](#)  
*output flags*
- [l4\\_umword\\_t l\\_flags](#)  
*local flags*

### 15.251.1 Detailed Description

Vcon attribute structure.

The flags members can be a combination of their respective enums.

See also

[L4\\_vcon\\_i\\_flags](#)  
[L4\\_vcon\\_o\\_flags](#)  
[L4\\_vcon\\_l\\_flags](#)

Examples

[examples/sys/isr/main.c](#).

Definition at line [187](#) of file [vcon.h](#).

### 15.251.2 Member Function Documentation

#### 15.251.2.1 set\_raw()

```
void l4_vcon_attr_t::set_raw () [inline]
```

Set terminal attributes to disable all special processing.

Removes all flags that would mangle the read or written characters. Also disables echoing and any special processing of characters.

Definition at line [450](#) of file [vcon.h](#).

References [l4\\_vcon\\_set\\_attr\\_raw\(\)](#).

Here is the call graph for this function:



The documentation for this struct was generated from the following file:


- [l4/sys/vcon.h](#)

## 15.252 l4\_vcpu\_arch\_state\_t Struct Reference

Architecture-specific vCPU state.

```
#include <__vcpu-arch.h>
```

Collaboration diagram for l4\_vcpu\_arch\_state\_t:



### 15.252.1 Detailed Description

Architecture-specific vCPU state.

Definition at line 74 of file [\\_\\_vcpu-arch.h](#).

The documentation for this struct was generated from the following files:


- [arm/l4/sys/\\_\\_vcpu-arch.h](#)
- [arm64/l4/sys/\\_\\_vcpu-arch.h](#)
- [amd64/l4/sys/\\_\\_vcpu-arch.h](#)

## 15.253 l4\_vcpu\_ipc\_regs\_t Struct Reference

vCPU message registers.

```
#include <__vcpu-arch.h>
```

Collaboration diagram for `l4_vcpu_ipc_regs_t`:



### 15.253.1 Detailed Description

vCPU message registers.

Definition at line 83 of file [\\_\\_vcpu-arch.h](#).

The documentation for this struct was generated from the following files:

- [arm/l4/sys/\\_\\_vcpu-arch.h](#)
- [arm64/l4/sys/\\_\\_vcpu-arch.h](#)
- [amd64/l4/sys/\\_\\_vcpu-arch.h](#)
- [x86/l4/sys/\\_\\_vcpu-arch.h](#)

## 15.254 l4\_vcpu\_regs\_t Struct Reference

vCPU registers.

```
#include <__vcpu-arch.h>
```

Collaboration diagram for l4\_vcpu\_regs\_t:

l4_vcpu_regs_t
+ pfa
+ err
+ sp
+ ip
+ flags
+ tpidruro
+ tpidrurw
+ r15
+ r14
+ r13
and 20 more...

### Data Fields

- [l4\\_umword\\_t](#) **pfa**  
*page fault address*
- [l4\\_umword\\_t](#) **err**  
*error code*
- [l4\\_umword\\_t](#) **sp**  
*stack pointer*
- [l4\\_umword\\_t](#) **ip**  
*instruction pointer*
- [l4\\_umword\\_t](#) **flags**  
*eflags*
- [l4\\_umword\\_t](#) **tpidruro**  
*Thread-ID register.*
- [l4\\_umword\\_t](#) **tpidrurw**  
*Thread-ID register.*
- [l4\\_umword\\_t](#) **r15**  
*r15 register*
- [l4\\_umword\\_t](#) **r14**

- r14 register*
- [l4\\_umword\\_t r13](#)
- r13 register*
- [l4\\_umword\\_t r12](#)
- r12 register*
- [l4\\_umword\\_t r11](#)
- r11 register*
- [l4\\_umword\\_t r10](#)
- r10 register*
- [l4\\_umword\\_t r9](#)
- r9 register*
- [l4\\_umword\\_t r8](#)
- r8 register*
- [l4\\_umword\\_t di](#)
- rdi register*
- [l4\\_umword\\_t si](#)
- rsi register*
- [l4\\_umword\\_t bp](#)
- rbp register*
- [l4\\_umword\\_t bx](#)
- rbx register*
- [l4\\_umword\\_t dx](#)
- rdx register*
- [l4\\_umword\\_t cx](#)
- rcx register*
- [l4\\_umword\\_t ax](#)
- rax register*
- [l4\\_umword\\_t trapno](#)
- trap number*
- [l4\\_umword\\_t cs](#)
- dummy*
- [l4\\_umword\\_t ss](#)
- ss register*
- [l4\\_umword\\_t es](#)
- es register*
- [l4\\_umword\\_t ds](#)
- ds register*
- [l4\\_umword\\_t gs](#)
- gs register*
- [l4\\_umword\\_t fs](#)
- fs register*
- [l4\\_umword\\_t dummy1](#)
- dummy*

### 15.254.1 Detailed Description

vCPU registers.

Definition at line 55 of file [\\_\\_vcpu-arch.h](#).



## 15.254.2 Field Documentation

### 15.254.2.1 ax

`l4_umword_t l4_vcpu_regs_t::ax`

rax register

eax register

Definition at line 77 of file [\\_\\_vcpu-arch.h](#).

### 15.254.2.2 bp

`l4_umword_t l4_vcpu_regs_t::bp`

rbp register

ebp register

Definition at line 72 of file [\\_\\_vcpu-arch.h](#).

### 15.254.2.3 bx

`l4_umword_t l4_vcpu_regs_t::bx`

rbx register

ebx register

Definition at line 74 of file [\\_\\_vcpu-arch.h](#).

### 15.254.2.4 cx

`l4_umword_t l4_vcpu_regs_t::cx`

rcx register

ecx register

Definition at line 76 of file [\\_\\_vcpu-arch.h](#).

### 15.254.2.5 di

`l4_umword_t l4_vcpu_regs_t::di`

rdi register

edi register

Definition at line 70 of file [\\_\\_vcpu-arch.h](#).

#### 15.254.2.6 dx

```
l4_umword_t l4_vcpu_regs_t::dx
```

rdx register

edx register

Definition at line 75 of file [\\_\\_vcpu-arch.h](#).

#### 15.254.2.7 si

```
l4_umword_t l4_vcpu_regs_t::si
```

rsi register

esi register

Definition at line 71 of file [\\_\\_vcpu-arch.h](#).

The documentation for this struct was generated from the following files:


- [arm/l4/sys/\\_\\_vcpu-arch.h](#)
- [amd64/l4/sys/\\_\\_vcpu-arch.h](#)
- [x86/l4/sys/\\_\\_vcpu-arch.h](#)

## 15.255 l4\_vcpu\_state\_t Struct Reference


State of a vCPU.

```
#include <vcpu.h>
```

Inheritance diagram for l4\_vcpu\_state\_t:



Collaboration diagram for `l4_vcpu_state_t`:



## Data Fields

- [l4\\_umword\\_t version](#)  
*vCPU ABI version.*
- [l4\\_umword\\_t user\\_data](#) [7]  
*User-specific data.*
- [l4\\_vcpu\\_regs\\_t r](#)

- Register state.*
- [l4\\_vcpu\\_ipc\\_regs\\_t](#) **i**  
*IPC state.*
- [l4\\_uint16\\_t](#) **state**  
*Current vCPU state. See [L4\\_vcpu\\_state\\_flags](#).*
- [l4\\_uint16\\_t](#) **saved\_state**  
*Saved vCPU state. See [L4\\_vcpu\\_state\\_flags](#).*
- [l4\\_uint16\\_t](#) **sticky\_flags**  
*Pending flags. See [L4\\_vcpu\\_sticky\\_flags](#).*
- [l4\\_cap\\_idx\\_t](#) **user\_task**  
*User task to use.*
- [l4\\_umword\\_t](#) **entry\_sp**  
*Stack pointer for entry (when coming from user task).*
- [l4\\_umword\\_t](#) **entry\_ip**  
*IP for entry.*
- [l4\\_vcpu\\_arch\\_state\\_t](#) **arch\_state**  
*Architecture-specific state.*

### 15.255.1 Detailed Description

State of a vCPU.

Definition at line 75 of file [vcpu.h](#).

### 15.255.2 Field Documentation

#### 15.255.2.1 version

```
l4\_umword\_t l4_vcpu_state_t::version
```

vCPU ABI version.

Set by the kernel and must be checked by the user for equality with [L4\\_VCPU\\_STATE\\_VERSION](#).

Definition at line 77 of file [vcpu.h](#).

The documentation for this struct was generated from the following file:


- [l4/sys/vcpu.h](#)

## 15.256 l4\_vm\_svm\_vmcb\_control\_area Struct Reference

VMCB structure for SVM VMs.

```
#include <__vm-svm.h>
```

Collaboration diagram for l4\_vm\_svm\_vmcb\_control\_area:



### 15.256.1 Detailed Description

VMCB structure for SVM VMs.

Definition at line 28 of file [\\_\\_vm-svm.h](#).

The documentation for this struct was generated from the following file:


- l4/sys/\_\_vm-svm.h

## 15.257 l4\_vm\_svm\_vmcb\_state\_save\_area Struct Reference

State save area structure for SVM VMs.

```
#include <__vm-svm.h>
```

Collaboration diagram for l4\_vm\_svm\_vmcb\_state\_save\_area:



### 15.257.1 Detailed Description

State save area structure for SVM VMs.

Definition at line 85 of file [\\_\\_vm-svm.h](#).

The documentation for this struct was generated from the following file:


- `l4/sys/__vm-svm.h`

## 15.258 l4\_vm\_svm\_vmcb\_state\_save\_area\_seg Struct Reference

State save area segment selector struct.

```
#include <__vm-svm.h>
```

Collaboration diagram for l4\_vm\_svm\_vmcb\_state\_save\_area\_seg:



### 15.258.1 Detailed Description

State save area segment selector struct.

Definition at line 73 of file [\\_\\_vm-svm.h](#).

The documentation for this struct was generated from the following file:

- l4/sys/\_\_vm-svm.h


## 15.259 l4\_vm\_svm\_vmcb\_t Struct Reference

Control structure for SVM VMs.

```
#include <__vm-svm.h>
```



Collaboration diagram for l4\_vm\_svm\_vmcb\_t:



### 15.259.1 Detailed Description

Control structure for SVM VMs.

Definition at line 154 of file [\\_\\_vm-svm.h](#).

The documentation for this struct was generated from the following file:


- `l4/sys/__vm-svm.h`

## 15.260 l4\_vm\_tz\_state Struct Reference

state structure for TrustZone VMs

```
#include <vm.h>
```

Collaboration diagram for l4\_vm\_tz\_state:



### 15.260.1 Detailed Description

state structure for TrustZone VMs

Definition at line 44 of file [vm.h](#).

The documentation for this struct was generated from the following file:


- [arm/l4/sys/vm.h](#)

## 15.261 l4\_vm\_vmx\_vcpu\_infos\_t Struct Reference

VMX information members.

```
#include <__vm-vmx.h>
```

Collaboration diagram for l4\_vm\_vmx\_vcpu\_infos\_t:



## Data Fields

- [l4\\_uint64\\_t caps](#) [[L4\\_VM\\_VMX\\_NUM\\_CAPS\\_REGS](#)]  
*Exported VMX capability registers. See [L4\\_vm\\_vmx\\_caps\\_regs](#).*
- [l4\\_uint32\\_t dfl1](#) [[L4\\_VM\\_VMX\\_NUM\\_DFL1\\_REGS](#)]  
*Exported VMX capability registers (default to 1 bits).*

### 15.261.1 Detailed Description

VMX information members.

Definition at line 239 of file [\\_\\_vm-vmx.h](#).

### 15.261.2 Field Documentation

#### 15.261.2.1 dfl1

[l4\\_uint32\\_t](#) [l4\\_vm\\_vmx\\_vcpu\\_infos\\_t::dfl1](#) [[L4\\_VM\\_VMX\\_NUM\\_DFL1\\_REGS](#)]

Exported VMX capability registers (default to 1 bits).

See [L4\\_vm\\_vmx\\_dfl1\\_regs](#).

Definition at line 246 of file [\\_\\_vm-vmx.h](#).

The documentation for this struct was generated from the following file:


- [l4/sys/\\_\\_vm-vmx.h](#)

## 15.262 l4\_vm\_vmx\_vcpu\_state\_t Struct Reference

VMX vCPU state.

```
#include <__vm-vmx.h>
```

Collaboration diagram for `l4_vm_vmx_vcpu_state_t`:



### 15.262.1 Detailed Description

VMX vCPU state.

This is a specialization of the generic vCPU state for VMX. This data structure represents the following memory layout:

- 0x000 - 0x1ff: Standard vCPU state (with padding). See [l4\\_vcpu\\_state\\_t](#).

- 0x200 - 0x3ff: VMX information members (with padding). See [l4\\_vm\\_vmx\\_vcpu\\_infos\\_t](#).
- 0x400 - 0xfff: VMX software VMCS. See [l4\\_vm\\_vmx\\_vcpu\\_vmcs\\_t](#).

#### Note

The memory layout is documented here for reference purposes. However, the users are strongly discouraged from accessing the data structure directly. The API functions defined in this file are the preferred way of achieving the functionality.

Definition at line 267 of file [\\_\\_vm-vmx.h](#).

The documentation for this struct was generated from the following file:


- l4/sys/\_\_vm-vmx.h

## 15.263 l4\_vm\_vmx\_vcpu\_vmcs\_t Struct Reference

VMX software VMCS.

```
#include <__vm-vmx.h>
```

Collaboration diagram for l4\_vm\_vmx\_vcpu\_vmcs\_t:



### 15.263.1 Detailed Description

VMX software VMCS.

This data structure represents the following memory layout:

- 0x000 - 0x007: Reserved (ignored by the kernel). In the hardware VMCS, the revision identifier and the abort indicator are stored in this area. Hereby we simply ignore these two entries.
- 0x008 - 0x00f: User space data (ignored by the kernel). This currently stores the pointer to a different software VMCS whose content has been loaded to this software VMCS.
- 0x010 - 0x013: VMCS field index of the software-defined CR2 field in the software VMCS.
- 0x014 - 0x017: Reserved.
- 0x018 - 0x01f: Capability of the vCPU context, i.e. the hardware VMCS object (with padding).
- 0x020 - 0x047: Software VMCS field offset table. See [l4\\_vmx\\_offset\\_table\\_t](#).
- 0x048 - 0x0bf: Reserved.
- 0x0c0 - 0xabf: Software VMCS fields (with padding).
- 0xac0 - 0xbff: Software VMCS fields dirty bitmap (with padding).

#### Note

The memory layout is documented here for reference purposes. However, the users are strongly discouraged from accessing the data structure directly. The API functions defined in this file are the preferred way of achieving the functionality.

Definition at line 205 of file [\\_\\_vm-vmx.h](#).

The documentation for this struct was generated from the following file:


- l4/sys/\_\_vm-vmx.h

## 15.264 l4\_vmx\_offset\_table\_t Struct Reference

Software VMCS field offset table.

```
#include <__vm-vmx.h>
```

Collaboration diagram for l4\_vmx\_offset\_table\_t:



### 15.264.1 Detailed Description

Software VMCS field offset table.

This data structure represents the following memory layout:

- 0x00 - 0x02: 3 offsets for 16-bit fields.
- 0x03: Reserved.
- 0x04 - 0x06: 3 offsets for 64-bit fields.
- 0x07: Reserved.
- 0x08 - 0x0a: 3 offsets for 32-bit fields.
- 0x0b: Reserved.
- 0x0c - 0x0e: 3 offsets for natural-width fields.
- 0x0f: Reserved.
- 0x10 - 0x12: 3 limits for 16-bit fields.
- 0x13: Reserved.
- 0x14 - 0x16: 3 limits for 64-bit fields.
- 0x17: Reserved.
- 0x18 - 0x1a: 3 limits for 32-bit fields.
- 0x1b: Reserved.
- 0x1c - 0x1e: 3 limits for natural-width fields.
- 0x1f: Reserved.
- 0x20 - 0x23: 4 index shifts.
- 0x24: Offset of the first software VMCS field.
- 0x25: Size of the software VMCS fields.
- 0x26 - 0x27: Reserved.

The offsets/limits in each size category are in the following order:

- Control fields.
- Read-only fields.
- Guest fields.

The index shifts are in the following order:

- 16-bit.
- 64-bit.
- 32-bit.
- Natural-width.

All offsets/limits/sizes are represented in a 64-byte granule.

The offsets (after being multiplied by 64) are indexes in the values array in [l4\\_vm\\_vmx\\_vcpu\\_vmcs\\_t](#) and bit indexes in the dirty\_bitmap array in [l4\\_vm\\_vmx\\_vcpu\\_vmcs\\_t](#).

The limits (after being multiplied by 64) represent the range of the available indexes.

**Note**

The memory layout is documented here for reference purposes. However, the users are strongly discouraged from accessing the data structure directly. The API functions defined in this file are the preferred way of achieving the functionality.

Definition at line 155 of file [\\_\\_vm-vmx.h](#).

The documentation for this struct was generated from the following file:


- l4/sys/\_\_vm-vmx.h

## 15.265 L4drivers::Mmio\_register\_block< MAX\_BITS > Struct Template Reference

An MMIO block with up to 64-bit register access (32-bit default) and little endian byte order.


```
#include <hw_mmio_register_block>
```

Inheritance diagram for L4drivers::Mmio\_register\_block< MAX\_BITS >:





Collaboration diagram for L4drivers::Mmio\_register\_block< MAX\_BITS >:



### 15.265.1 Detailed Description

```
template<unsigned MAX_BITS = 32>
struct L4drivers::Mmio_register_block< MAX_BITS >
```

An MMIO block with up to 64-bit register access (32-bit default) and little endian byte order.

Definition at line 45 of file [hw\\_mmio\\_register\\_block](#).

The documentation for this struct was generated from the following file:


- pkg/drivers-frst/include/hw\_mmio\_register\_block

## 15.266 L4drivers::Register\_block< MAX\_BITS, BLOCK > Class Template Reference

Handles a reference to a register block of the given maximum access width.

```
#include <hw_register_block>
```

Collaboration diagram for L4drivers::Register\_block< MAX\_BITS, BLOCK >:



### Public Member Functions

- template<unsigned BITS>  
Ro\_register\_tmpl< BITS, Block > r (unsigned offset) const  
*Read only access to register at offset offset.*
- Ro\_register operator[] (unsigned offset) const  
*Read only access to register at offset offset.*
- template<unsigned BITS>  
Register\_tmpl< BITS, Block > r (unsigned offset)  
*Read/write access to register at offset offset.*
- Register operator[] (unsigned offset)  
*Read/write access to register at offset offset.*

### 15.266.1 Detailed Description

```
template<unsigned MAX_BITS, typename BLOCK = Register_block_tmpl< Register_block_base<MAX_BITS> >>
class L4drivers::Register_block< MAX_BITS, BLOCK >
```

Handles a reference to a register block of the given maximum access width.

Register block.

## Template Parameters

<i>MAX_BITS</i>	Maximum access width for the registers in this block.
<i>BLOCK</i>	Type implementing the register accesses ( <code>read&lt;&gt;()</code> , <code>write&lt;&gt;()</code> , <code>modify&lt;&gt;()</code> , <code>set&lt;&gt;()</code> , and <code>clear&lt;&gt;()</code> ).

Provides access to registers in this block via `r<WIDTH>()` and `operator[]()`.

### Example usage:

```
void test()
{
    // create a register block reference for max. 16bit accesses, using a
    // MMIO register block implementation (at address 0x1000).
    Hw::Register_block<16> regs = new Hw::Mmio_register_block<16>(0x1000);

    // Alternatively it is allowed to use an implementation that allows
    // wider access than actually needed.
    Hw::Register_block<16> regs = new Hw::Mmio_register_block<32>(0x1000);

    // read a 16bit register at offset 8byte
    unsigned short x = regs.r<16>(8);
    unsigned short x1 = regs[8];      // alternative

    // read an 8bit register at offset 0byte
    unsigned v = regs.r<8>(0);

    // do a 16bit write to register at offset 2byte (four variants)
    regs[2] = 22;
    regs.r<16>(2) = 22;
    regs[2].write(22);
    regs.r<16>().write(22);

    // do an 8bit write (two variants)
    regs.r<8>(0) = 9;
    regs.r<8>(0).write(9);

    // do 16bit read-modify-write (two variants)
    regs[4].modify(0xf, 3); // clear 4 lowest bits and set them to 3
    regs.r<16>(4).modify(0xf, 3);

    // do 8bit read-modify-write
    regs.r<8>(0).modify(0xf, 3);

    // fails to compile, because of too wide access
    // (32 bit access but regs is Hw::Register_block<16>)
    unsigned long v = regs.r<32>(4)
}
```

Definition at line 330 of file `hw_register_block`.

## 15.266.2 Member Function Documentation

### 15.266.2.1 `operator[]()` [1/2]

```
template<unsigned MAX_BITS, typename BLOCK = Register_block_tmpl< Register_block_base<MAX_BITS> >>
Register L4drivers::Register_block< MAX_BITS, BLOCK >::operator[] (
    unsigned offset) [inline]
```

Read/write access to register at offset *offset*.

### Parameters

<i>offset</i>	The offset of the register within the register file.
---------------	--


**Returns**

register object allowing read and write access with width *MAX\_BITS*.

Definition at line 385 of file [hw\\_register\\_block](#).

References [r\(\)](#).

Here is the call graph for this function:

**15.266.2.2 operator[]() [2/2]**

```

template<unsigned MAX_BITS, typename BLOCK = Register_block_tmpl< Register_block_base<MAX_BITS> >>
Ro_register L4drivers::Register_block< MAX_BITS, BLOCK >::operator[] (
    unsigned offset) const [inline]
  
```

Read only access to register at offset *offset*.

**Parameters**

<i>offset</i>	The offset of the register within the register file.
---------------	--


**Returns**

register object allowing read only access with width *MAX\_BITS*.

Definition at line 365 of file [hw\\_register\\_block](#).

References [r\(\)](#).

Here is the call graph for this function:



**15.266.2.3** `r()` [1/2]

```
template<unsigned MAX_BITS, typename BLOCK = Register_block_tmpl< Register_block_base<MAX_BITS> >>
template<unsigned BITS>
Register_tmpl< BITS, Block > L4drivers::Register_block< MAX_BITS, BLOCK >::r (
    unsigned offset) [inline]
```

Read/write access to register at offset *offset*.

**Template Parameters**

<i>BITS</i>	the access width in bits for the register.
-------------	--

**Parameters**

<i>offset</i>	The offset of the register within the register file.
---------------	--

**Returns**

register object allowing read and write access with width *BITS*.

Definition at line 376 of file [hw\\_register\\_block](#).

**15.266.2.4** `r()` [2/2]

```
template<unsigned MAX_BITS, typename BLOCK = Register_block_tmpl< Register_block_base<MAX_BITS> >>
template<unsigned BITS>
Ro_register_tmpl< BITS, Block > L4drivers::Register_block< MAX_BITS, BLOCK >::r (
    unsigned offset) const [inline]
```

Read only access to register at offset *offset*.

**Template Parameters**

<i>BITS</i>	the access width in bits for the register.
-------------	--

**Parameters**

<i>offset</i>	The offset of the register within the register file.
---------------	--


**Returns**

register object allowing read only access with width *BITS*.

Definition at line 357 of file [hw\\_register\\_block](#).

Referenced by [operator\[\]\(\)](#), and [operator\[\]\(\)](#).

Here is the caller graph for this function:




The documentation for this class was generated from the following file:

- `pkg/drivers-frst/include/hw_register_block`


## 15.267 L4drivers::Register\_block\_base< MAX\_BITS > Struct Template Reference

Abstract register block interface.

Inheritance diagram for L4drivers::Register\_block\_base< MAX\_BITS >:



Collaboration diagram for L4drivers::Register\_block\_base< MAX\_BITS >:



### 15.267.1 Detailed Description

```
template<unsigned MAX_BITS = 32>
struct L4drivers::Register_block_base< MAX_BITS >
```

Abstract register block interface.

#### Template Parameters

<i>MAX_BITS</i>	The maximum access width for the registers.
-----------------	---

This interfaces is based on virtual `do_read_<xx>` and `do_write_<xx>` methods that have to be implemented up to the maximum access width.

Definition at line 72 of file [hw\\_register\\_block](#).


The documentation for this struct was generated from the following file:

- `pkg/drivers-frst/include/hw_register_block`


## 15.268 L4drivers::Register\_block\_impl< BASE, MAX\_BITS > Struct Template Reference

Implementation helper for register blocks.

Inheritance diagram for L4drivers::Register\_block\_impl< BASE, MAX\_BITS >:



Collaboration diagram for L4drivers::Register\_block\_impl< BASE, MAX\_BITS >:





### 15.268.1 Detailed Description

```
template<typename BASE, unsigned MAX_BITS = 32>
struct L4drivers::Register_block_impl< BASE, MAX_BITS >
```

Implementation helper for register blocks.

#### Parameters

<i>BASE</i>	The class implementing read<> and write<> template functions for accessing the registers. This class must inherit from <a href="#">Register_block_impl</a> .
<i>MAX_BITS</i>	The maximum access width for the register file. Supported values are 8, 16, 32, or 64.

This template allows easy implementation of register files by providing read<> and write<> template functions, see [Mmio\\_register\\_block](#) as an example.

Definition at line 455 of file [hw\\_register\\_block](#).

The documentation for this struct was generated from the following file:


- [pkg/drivers-frst/include/hw\\_register\\_block](#)

## 15.269 L4drivers::Register\_block\_tmpl< BLOCK > Class Template Reference


Helper template that translates to the [Register\\_block\\_base](#) interface.

```
#include <hw_register_block>
```

Inheritance diagram for L4drivers::Register\_block\_tmpl< BLOCK >:



Collaboration diagram for L4drivers::Register\_block\_tmpl< BLOCK >:



### 15.269.1 Detailed Description

```
template<typename BLOCK>
class L4drivers::Register_block_tmpl< BLOCK >
```

Helper template that translates to the [Register\\_block\\_base](#) interface.

#### Template Parameters

<i>BLOCK</i>	The type of the <a href="#">Register_block_base</a> interface to use.
--------------	---

This helper translates `read<T>()`, `write<T>()`, `set<T>()`, `clear<T>()`, and `modify<T>()` calls to `BLOCK::do_↵read_<xx>` and `BLOCK::do_write_<xx>`.

Definition at line [156](#) of file [hw\\_register\\_block](#).

The documentation for this class was generated from the following file:


- `pkg/drivers-frst/include/hw_register_block`

## 15.270 L4drivers::Register\_tmpl< BITS, BLOCK > Class Template Reference


Single hardware register inside a [Register\\_block\\_base](#) interface.

```
#include <hw_register_block>
```

Inheritance diagram for L4drivers::Register\_tmpl< BITS, BLOCK >:



Collaboration diagram for L4drivers::Register\_tmpl< BITS, BLOCK >:



### Public Member Functions

- `Register_tmpl & operator= (value_type val)`  
*write val into the hardware register.*
- `void write (value_type val)`  
*write val into the hardware register.*
- `value_type set (value_type set_bits)`  
*set bits in set\_bits in the hardware register.*
- `value_type clear (value_type clear_bits)`  
*clears bits in clear\_bits in the hardware register.*
- `value_type modify (value_type clear_bits, value_type set_bits)`  
*clears bits in clear\_bits and sets bits in set\_bits in the hardware register.*

### Public Member Functions inherited from **L4drivers::Ro\_register\_tmpl< BITS, BLOCK >**

- `operator value_type () const`  
*read the value from the hardware register.*
- `value_type read () const`  
*read the value from the hardware register.*

## 15.270.1 Detailed Description

template<unsigned BITS, typename BLOCK>  
class L4drivers::Register\_tmpl< BITS, BLOCK >

Single hardware register inside a [Register\\_block\\_base](#) interface.

### Template Parameters

<i>BITS</i>	The access width for the register in bits.
<i>BLOCK</i>	the type of the <a href="#">Register_block_base</a> interface.

### Note

Objects of this type must be used only in temporary contexts not in global, class, or object scope.

Definition at line 237 of file [hw\\_register\\_block](#).

## 15.270.2 Member Function Documentation

### 15.270.2.1 clear()

```
template<unsigned BITS, typename BLOCK>
value_type L4drivers::Register_tmpl< BITS, BLOCK >::clear (
    value_type clear_bits) [inline]
```

clears bits in *clear\_bits* in the hardware register.

### Parameters

<i>clear_bits</i>	bits to be cleared within the hardware register.
-------------------	--


This is a read-modify-write function that does a logical and of the old value from the register with the negated value of *clear\_bits*.

```
unsigned old_value = read();
write(old_value & ~clear_bits);
```

Definition at line 290 of file [hw\\_register\\_block](#).

Referenced by [L4drivers::Register\\_tmpl< MAX\\_BITS, Block >::clear\(\)](#).

Here is the caller graph for this function:



### 15.270.2.2 modify()

```
template<unsigned BITS, typename BLOCK>
value_type L4drivers::Register_tmpl< BITS, BLOCK >::modify (
    value_type clear_bits,
    value_type set_bits) [inline]
```

clears bits in *clear\_bits* and sets bits in *set\_bits* in the hardware register.

#### Parameters

<i>clear_bits</i>	bits to be cleared within the hardware register.
<i>set_bits</i>	bits to set in the hardware register.


This is a read-modify-write function that first does a logical and of the old value from the register with the negated value of *clear\_bits* and then does a logical or with *set\_bits*.

```
unsigned old_value = read();
write((old_value & ~clear_bits) | set_bits);
```

Definition at line 308 of file [hw\\_register\\_block](#).

Referenced by [L4drivers::Register\\_tmpl< MAX\\_BITS, Block >::modify\(\)](#).

Here is the caller graph for this function:



### 15.270.2.3 operator=()

```
template<unsigned BITS, typename BLOCK>
Register_tmpl & L4drivers::Register_tmpl< BITS, BLOCK >::operator= (
    value_type val) [inline]
```

write *val* into the hardware register.

#### Parameters

<i>val</i>	the value to write into the hardware register.
------------	--

Definition at line 252 of file [hw\\_register\\_block](#).

#### 15.270.2.4 set()

```
template<unsigned BITS, typename BLOCK>
value_type L4drivers::Register_tmpl< BITS, BLOCK >::set (
    value_type set_bits) [inline]
```

set bits in *set\_bits* in the hardware register.

##### Parameters

<i>set_bits</i>	bits to be set within the hardware register.
-----------------	--

This is a read-modify-write function that does a logical or of the old value from the register with *set\_bits*.

```
unsigned old_value = read();
write(old_value | set_bits);
```

Definition at line 274 of file [hw\\_register\\_block](#).

Referenced by [L4drivers::Register\\_tmpl< MAX\\_BITS, Block >::set\(\)](#).

Here is the caller graph for this function:



#### 15.270.2.5 write()

```
template<unsigned BITS, typename BLOCK>
void L4drivers::Register_tmpl< BITS, BLOCK >::write (
    value_type val) [inline]
```

write *val* into the hardware register.


##### Parameters

<i>val</i>	the value to write into the hardware register.
------------	--

Definition at line 259 of file [hw\\_register\\_block](#).

Referenced by [L4drivers::Register\\_tmpl< MAX\\_BITS, Block >::operator=\(\)](#), and [L4drivers::Register\\_tmpl< MAX\\_BITS, Block >::write\(\)](#).

Here is the caller graph for this function:



The documentation for this class was generated from the following file:


- pkg/drivers-frst/include/hw\_register\_block

## 15.271 L4drivers::Ro\_register\_block< MAX\_BITS, BLOCK > Class Template Reference

Handles a reference to a read only register block of the given maximum access width.

```
#include <hw_register_block>
```

Collaboration diagram for L4drivers::Ro\_register\_block< MAX\_BITS, BLOCK >:



### Public Member Functions

- Ro\_register [operator\[\]](#) (unsigned offset) const  
*Read only access to register at offset offset.*
- template<unsigned BITS>  
[Ro\\_register\\_tmpl](#)< BITS, Block > [r](#) (unsigned offset) const  
*Read only access to register at offset offset.*



## 15.271.1 Detailed Description

```
template<unsigned MAX_BITS, typename BLOCK = Register_block_tmpl< Register_block_base<MAX_↵
BITS> const >>
class L4drivers::Ro_register_block< MAX_BITS, BLOCK >
```

Handles a reference to a read only register block of the given maximum access width.

### Template Parameters

<i>MAX_BITS</i>	Maximum access width for the registers in this block.
<i>BLOCK</i>	Type implementing the register accesses (read<>()),

Provides read only access to registers in this block via [r<WIDTH>\(\)](#) and [operator\[\]\(\)](#).

Definition at line [404](#) of file [hw\\_register\\_block](#).

## 15.271.2 Member Function Documentation

### 15.271.2.1 operator[]()

```
template<unsigned MAX_BITS, typename BLOCK = Register_block_tmpl< Register_block_base<MAX_↵
BITS> const >>
Ro_register L4drivers::Ro\_register\_block< MAX_BITS, BLOCK >::operator[] (
    unsigned offset) const [inline]
```

Read only access to register at offset *offset*.

### Parameters

<i>offset</i>	The offset of the register within the register file.
---------------	--

### Returns

register object allowing read only access with width *MAX\_BITS*.

Definition at line [426](#) of file [hw\\_register\\_block](#).

**15.271.2.2 r()**

```
template<unsigned MAX_BITS, typename BLOCK = Register_block_tmpl< Register_block_base<MAX_BITS> const >>
template<unsigned BITS>
Ro_register_tmpl< BITS, Block > L4drivers::Ro_register_block< MAX_BITS, BLOCK >::r (
    unsigned offset) const [inline]
```

Read only access to register at offset *offset*.

**Template Parameters**

<i>BITS</i>	the access width in bits for the register.
-------------	--

**Parameters**

<i>offset</i>	The offset of the register within the register file.
---------------	--

**Returns**

register object allowing read only access with width *BITS*.

Definition at line 436 of file [hw\\_register\\_block](#).

The documentation for this class was generated from the following file:


- pkg/drivers-frst/include/hw\_register\_block

## 15.272 L4drivers::Ro\_register\_tmpl< BITS, BLOCK > Class Template Reference


Single read only register inside a [Register\\_block\\_base](#) interface.

```
#include <hw_register_block>
```

Inheritance diagram for L4drivers::Ro\_register\_tmpl< BITS, BLOCK >:



Collaboration diagram for L4drivers::Ro\_register\_tmpl< BITS, BLOCK >:



## Public Member Functions

- `operator value_type ()` const  
*read the value from the hardware register.*
- `value_type read ()` const  
*read the value from the hardware register.*

### 15.272.1 Detailed Description

```
template<unsigned BITS, typename BLOCK>
class L4drivers::Ro_register_tmpl< BITS, BLOCK >
```

Single read only register inside a [Register\\_block\\_base](#) interface.

#### Template Parameters

<i>BITS</i>	The access with of the register in bits.
<i>BLOCK</i>	The type for the <a href="#">Register_block_base</a> interface.

#### Note

Objects of this type must be used only in temporary contexts not in global, class, or object scope.

Allows simple read only access to a hardware register.

Definition at line 201 of file [hw\\_register\\_block](#).

### 15.272.2 Member Function Documentation

#### 15.272.2.1 operator value\_type()

```
template<unsigned BITS, typename BLOCK>
L4drivers::Ro_register_tmpl< BITS, BLOCK >::operator value_type () const [inline]
```

read the value from the hardware register.

#### Returns

value read from the hardware register.

Definition at line 217 of file [hw\\_register\\_block](#).

#### 15.272.2.2 read()

```
template<unsigned BITS, typename BLOCK>
value_type L4drivers::Ro_register_tmpl< BITS, BLOCK >::read () const [inline]
```

read the value from the hardware register.


**Returns**

value from the hardware register.

Definition at line 224 of file [hw\\_register\\_block](#).

Referenced by [L4drivers::value\\_type< BITS, BLOCK >::operator value\\_type\(\)](#), and [L4drivers::value\\_type< BITS, BLOCK >::read\(\)](#).

Here is the caller graph for this function:



The documentation for this class was generated from the following file:


- `pkg/drivers-frst/include/hw_register_block`

## 15.273 L4Re::Cap\_alloc Class Reference


Capability allocator interface.

```
#include <cap_alloc>
```

Inheritance diagram for L4Re::Cap\_alloc:



Collaboration diagram for L4Re::Cap\_alloc:



## Public Member Functions

- virtual [L4::Cap](#)< void > [alloc](#) () noexcept=0  
*Allocate a capability.*
- template<typename T>  
[L4::Cap](#)< T > [alloc](#) () noexcept  
*Allocate a capability.*
- virtual void [free](#) ([L4::Cap](#)< void > cap, [l4\\_cap\\_idx\\_t](#) task=[L4\\_INVALID\\_CAP](#), unsigned unmap\_↔  
flags=[L4\\_FP\\_ALL\\_SPACES](#)) noexcept=0  
*Free a capability.*

## 15.273.1 Detailed Description

Capability allocator interface.

Definition at line 30 of file [cap\\_alloc](#).

## 15.273.2 Member Function Documentation

### 15.273.2.1 [alloc](#)() [1/2]

```
template<typename T>
L4::Cap< T > L4Re::Cap_alloc::alloc () [inline], [noexcept]
```

Allocate a capability.


**Returns**

Capability of type T

Definition at line 55 of file [cap\\_alloc](#).

References [alloc\(\)](#), and [L4::cap\\_cast\(\)](#).

Here is the call graph for this function:

**15.273.2.2 alloc() [2/2]**

```
virtual L4::Cap< void > L4Re::Cap_alloc::alloc () [pure virtual], [noexcept]
```

Allocate a capability.


**Returns**

Capability of type void

Implemented in [L4Re::Util::\\_Cap\\_alloc](#), and [L4Re::Util::\\_Cap\\_alloc](#).

Referenced by [alloc\(\)](#), [L4Re::make\\_shared\\_cap\(\)](#), [L4Re::make\\_shared\\_del\\_cap\(\)](#), [L4Re::make\\_unique\\_cap\(\)](#), and [L4Re::make\\_unique\\_del\\_cap\(\)](#).

Here is the caller graph for this function:



### 15.273.2.3 free()

```
virtual void L4Re::Cap_alloc::free (
    L4::Cap< void > cap,
    l4_cap_idx_t task = L4_INVALID_CAP,
    unsigned unmap_flags = L4_FP_ALL_SPACES) [pure virtual], [noexcept]
```

Free a capability.

#### Parameters

<i>cap</i>	Capability to free.
<i>task</i>	If set, task to unmap the capability from.
<i>unmap_flags</i>	Flags for unmap, see <a href="#">l4_unmap_flags_t</a> .

Implemented in [L4Re::Util::\\_Cap\\_alloc](#).

References [L4Re::L4\\_FP\\_ALL\\_SPACES](#), and [L4\\_INVALID\\_CAP](#).

The documentation for this class was generated from the following file:

- [l4/re/cap\\_alloc](#)


## 15.274 L4Re::Console Class Reference

[Console](#) class.


```
#include <console>
```



Inheritance diagram for L4Re::Console:



Collaboration diagram for L4Re::Console:



### Additional Inherited Members

### Protected Types inherited from

**L4::Kobject\_2t< Console, Video::Goos, Event, L4::PROTO\_EMPTY >**

- typedef Console [Class](#)  
The target interface type (inheriting from [Kobject\\_t](#)).
- typedef Typeid::Iface< PROTO, Console > [\\_\\_Iface](#)  
The interface description for the derived class.
- typedef Typeid::Merge\_list< Typeid::Iface\_list< [\\_\\_Iface](#) >, Typeid::Merge\_list< typename Video::Goos::\_↔  
\_Iface\_list, typename Event::\_Iface\_list > > [\\_\\_Iface\\_list](#)  
The list of all RPC interfaces provided directly or through inheritance.

**Protected Member Functions inherited from****[L4::Kobject\\_2t< Console, Video::Goos, Event, L4::PROTO\\_EMPTY >](#)**

- [L4::Cap< Class > c \(\)](#) const noexcept

*Get the capability to ourselves.***Static Protected Member Functions inherited from****[L4::Kobject\\_2t< Console, Video::Goos, Event, L4::PROTO\\_EMPTY >](#)**

- static void [\\_\\_check\\_protocols\\_\\_ \(\)](#) noexcept

*Helper to check for protocol conflicts.***15.274.1 Detailed Description**

[Console](#) class.

Definition at line 28 of file [console](#).

The documentation for this class was generated from the following file:


- [l4/re/console](#)

**15.275 L4Re::Core::Ref\_ptr< T, CNT > Class Template Reference**

A reference-counting pointer with automatic cleanup.

```
#include <ref_ptr>
```

Inheritance diagram for L4Re::Core::Ref\_ptr< T, CNT >:



Collaboration diagram for L4Re::Core::Ref\_ptr< T, CNT >:

L4Re::Core::Ref_ptr < T, CNT >	
+	Ref_ptr()
+	Ref_ptr()
+	Ref_ptr()
+	Ref_ptr()
+	Ref_ptr()
+	get()
+	ptr()
+	release()

## Public Member Functions

- **Ref\_ptr** () noexcept  
*Default constructor creates a pointer with no managed object.*
- **Ref\_ptr** (Wp const &o) noexcept  
*Create a shared pointer from a weak pointer.*
- **Ref\_ptr** (decltype(nullptr) n) noexcept  
*allow creation from `nullptr`*
- template<typename X>  
**Ref\_ptr** (X \*o) noexcept  
*Create a shared pointer from a raw pointer.*
- **Ref\_ptr** (T \*o, bool d) noexcept  
*Create a shared pointer from a raw pointer without creating a new reference.*
- T \* **get** () const noexcept  
*Return a raw pointer to the object this shared pointer points to.*
- T \* **ptr** () const noexcept  
*Return a raw pointer to the object this shared pointer points to.*
- T \* **release** () noexcept  
*Release the shared pointer without removing the reference.*

## 15.275.1 Detailed Description

```
template<typename T = void, template< typename X > class CNT = Default_ref_counter>
class L4Re::Core::Ref_ptr< T, CNT >
```

A reference-counting pointer with automatic cleanup.

## Template Parameters

<i>T</i>	Type of object the pointer points to.
<i>CNT</i>	Type of management class that manages the life time of the object.

This pointer is similar to the standard C++-11 `shared_ptr` but it does the reference counting directly in the object being pointed to, so that no additional management structures need to be allocated from the heap.

Classes that use this pointer type must implement two functions:

```
int remove_ref()
```

is called when a reference is removed and must return 0 when there are no further references to the object.

```
void add_ref()
```

is called when another `ref_ptr` to the object is created.

`Ref_obj` provides a simple implementation of this interface from which classes may inherit.

Definition at line 70 of file [ref\\_ptr](#).

## 15.275.2 Constructor & Destructor Documentation

### 15.275.2.1 `Ref_ptr()` [1/3]

```
template<typename T = void, template< typename X > class CNT = Default_ref_counter>
cxx::Ref_ptr< T, CNT >::Ref_ptr (
    Wp const & o) [inline], [noexcept]
```

Create a shared pointer from a weak pointer.

Increases references.

Definition at line 88 of file [ref\\_ptr](#).

### 15.275.2.2 `Ref_ptr()` [2/3]

```
template<typename T = void, template< typename X > class CNT = Default_ref_counter>
template<typename X>
cxx::Ref_ptr< T, CNT >::Ref_ptr (
    X * o) [inline], [explicit], [noexcept]
```

Create a shared pointer from a raw pointer.

In contrast to C++11 `shared_ptr` it is safe to use this constructor multiple times and have the same reference counter.

Definition at line 101 of file [ref\\_ptr](#).

**15.275.2.3 Ref\_ptr()** [3/3]

```
template<typename T = void, template< typename X > class CNT = Default_ref_counter>
cxx::Ref_ptr< T, CNT >::Ref_ptr (
    T * o,
    bool d) [inline], [noexcept]
```

Create a shared pointer from a raw pointer without creating a new reference.

**Parameters**

<i>o</i>	Pointer to the object.
<i>d</i>	Dummy parameter to select this constructor at compile time. The value may be true or false.

This is the counterpart to [release\(\)](#).

Definition at line [114](#) of file [ref\\_ptr](#).

**15.275.3 Member Function Documentation****15.275.3.1 get()**

```
template<typename T = void, template< typename X > class CNT = Default_ref_counter>
T * cxx::Ref_ptr< T, CNT >::get () const [inline], [noexcept]
```

Return a raw pointer to the object this shared pointer points to.

This does not release the pointer or decrease the reference count.

Definition at line [121](#) of file [ref\\_ptr](#).

**15.275.3.2 ptr()**

```
template<typename T = void, template< typename X > class CNT = Default_ref_counter>
T * cxx::Ref_ptr< T, CNT >::ptr () const [inline], [noexcept]
```

Return a raw pointer to the object this shared pointer points to.

This does not release the pointer or decrease the reference count.

Definition at line [127](#) of file [ref\\_ptr](#).

**15.275.3.3 release()**

```
template<typename T = void, template< typename X > class CNT = Default_ref_counter>
T * cxx::Ref_ptr< T, CNT >::release () [inline], [noexcept]
```

Release the shared pointer without removing the reference.

**Returns**

A raw pointer to the managed object.

Definition at line [138](#) of file [ref\\_ptr](#).

The documentation for this class was generated from the following file:


- [l4/cxx/ref\\_ptr](#)

## 15.276 L4Re::Dataspace Class Reference

Interface for memory-like objects.


```
#include <dataspace>
```

Inheritance diagram for L4Re::Dataspace:





Collaboration diagram for L4Re::Dataspace:



## Data Structures

- struct [F](#)  
*Dataspace flags definitions.*
- struct [Stats](#)  
*Information about the dataspace.*

## Public Member Functions

- [l4\\_ret\\_t map](#) (Offset `offset`, Flags `flags`, Map\_addr `local_addr`, Map\_addr `min_addr`, Map\_addr `max_addr`, `L4::Cap< L4::Task > dst=L4::Cap< L4::Task >::Invalid`) const noexcept

- Request a flexpage mapping from the dataspace.*
- [l4\\_ret\\_t map\\_region](#) (Offset offset, Flags [flags](#), Map\_addr min\_addr, Map\_addr max\_addr, [L4::Cap](#)< [L4::Task](#) > dst=[L4::Cap](#)< [L4::Task](#) >::Invalid) const noexcept  
*Map a part of a dataspace into a local memory area.*
- [l4\\_ret\\_t clear](#) (Offset offset, Size [size](#))  
*Clear parts of a dataspace.*
- [l4\\_ret\\_t allocate](#) (Offset offset, Size [size](#))  
*Allocate a range in the dataspace.*
- [l4\\_ret\\_t copy\\_in](#) (Offset dst\_offs, [L4::lpc::Cap](#)< Dataspace > src, Offset src\_offs, Size [size](#))  
*Copy contents from another dataspace.*
- Size [size](#) () const noexcept  
*Get size of a dataspace.*
- Flags [flags](#) () const noexcept  
*Get flags of the dataspace.*
- [l4\\_ret\\_t info](#) ([Stats](#) \*stats)  
*Get information on the dataspace.*
- long [map\\_info](#) ([l4\\_addr\\_t](#) \*start\_addr, [l4\\_addr\\_t](#) \*end\_addr)  
*Get mapping range of dataspace.*

## Public Member Functions inherited from [L4::Kobject](#)

- [l4\\_msgtag\\_t dec\\_refcnt](#) ([l4\\_mword\\_t](#) diff, [l4\\_utcb\\_t](#) \*utcb=[l4\\_utcb](#)())  
*Decrement the in kernel reference counter for the object.*

## Additional Inherited Members

## Protected Types inherited from

[L4::Kobject\\_t](#)< [Dataspace](#), [L4::Kobject](#), [L4RE\\_PROTO\\_DATASPACE](#), [L4::Type\\_info::Demand\\_t](#)< 1 > >

- typedef Dataspace **Class**  
*The target interface type (inheriting from [Kobject\\_t](#)).*
- typedef Typeid::Iface< PROTO, Dataspace > **\_\_Iface**  
*The interface description for the derived class.*
- typedef Typeid::Merge\_list< Typeid::Iface\_list< [\\_\\_Iface](#) >, typename [L4::Kobject::\\_\\_Iface\\_list](#) > **\_\_Iface\_list**  
*The list of all RPC interfaces provided directly or through inheritance.*

## Protected Member Functions inherited from

[L4::Kobject\\_t](#)< [Dataspace](#), [L4::Kobject](#), [L4RE\\_PROTO\\_DATASPACE](#), [L4::Type\\_info::Demand\\_t](#)< 1 > >

- [L4::Cap](#)< [Class](#) > **c** () const noexcept  
*Get the capability to ourselves.*

## Protected Member Functions inherited from [L4::Kobject](#)

- [l4\\_cap\\_idx\\_t cap](#) () const noexcept  
*Return capability selector.*

**Static Protected Member Functions inherited from****L4::Kobject\_t< Dataspace, L4::Kobject, L4RE\_PROTO\_DATASPACE, L4::Type\_info::Demand\_t< 1 > >**

- static void **\_\_check\_protocols\_\_** () noexcept

*Helper to check for protocol conflicts.*

**15.276.1 Detailed Description**

Interface for memory-like objects.

Dataspaces are a central abstraction provided by [L4Re](#). A dataspace is an abstraction for any thing that is available via usual memory access instructions. A dataspace can be a file, as well as the memory-mapped registers of a device, or anonymous memory, such as a heap.

The dataspace interface defines a set of methods that allow any kind of dataspace to be attached (mapped) to the virtual address space of an [L4](#) task and then be accessed via memory-access instructions. The [L4Re::Rm](#) interface can be used to attach a dataspace to a virtual address space of a task paged by a certain instance of a region map.

**Include File**

```
#include <l4/re/dataspace>
```

**Examples**

[examples/libs/l4re/c++/mem\\_alloc/ma+rm.cc](#), [examples/libs/l4re/c++/shared\\_ds/ds\\_clnt.cc](#), and [examples/libs/l4re/c++/shared](#)

Definition at line 50 of file [dataspace](#).

**15.276.2 Member Function Documentation****15.276.2.1 allocate()**

```
l4_ret_t L4Re::Dataspace::allocate (
    Offset offset,
    Size size)
```

Allocate a range in the dataspace.

**Parameters**

<i>offset</i>	Offset in the dataspace, in bytes.
<i>size</i>	Size of the range, in bytes.

**Return values**

<i>L4_EOK</i>	Success
---------------	---------

<code>-L4_ERANGE</code>	Given range is outside the dataspace. (A dataspace provider may also silently ignore areas outside the dataspace.)
<code>-L4_ENOMEM</code>	Not enough memory available.
<code>&lt; 0</code>	IPC errors


On success, at least the given range is guaranteed to be allocated. The dataspace manager may also allocate more memory due to page granularity.

The memory is allocated with the same rights as the dataspace capability.

References [allocate\(\)](#), [copy\\_in\(\)](#), and [size\(\)](#).

Referenced by [allocate\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 15.276.2.2 clear()

```

l4_ret_t L4Re::Dataspace::clear (
    Offset offset,
    Size size)

```

Clear parts of a dataspace.

#### Parameters

<i>offset</i>	Offset within dataspace (in bytes).
<i>size</i>	Size of region to clear (in bytes).

**Return values**

$\geq 0$	Success.
<code>-L4_ERANGE</code>	Given range is outside the dataspace. (A dataspace provider may also silently ignore areas outside the dataspace.)
<code>-L4_EACCESS</code>	No <code>L4_CAP_FPAGE_W</code> right on dataspace capability.
$< 0$	IPC errors

Zeroes out the memory. Depending on the type of memory the memory could also be deallocated and replaced by a shared zero-page.

References [clear\(\)](#), and [size\(\)](#).

Referenced by [clear\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:

**15.276.2.3 copy\_in()**

```

l4_ret_t L4Re::Dataspace::copy_in (
    Offset dst_offs,
    L4::Ipc::Cap< Dataspace > src,
    Offset src_offs,
    Size size)
  
```

Copy contents from another dataspace.

**Parameters**

<i>dst_offs</i>	Offset in destination dataspace.
<i>src</i>	Source dataspace to copy from.
<i>src_offs</i>	Offset in the source dataspace.
<i>size</i>	Size to copy (in bytes).

**Return values**

<i>L4_EOK</i>	Success
<i>-L4_EACCESS</i>	No <a href="#">L4_CAP_FPAGE_W</a> right on the destination dataspace.
<i>-L4_EINVAL</i>	Invalid parameter supplied.
<i>&lt; 0</i>	IPC errors

The copy operation may use copy-on-write mechanisms. The operation may also fail if both dataspaces are not from the same dataspace manager or the dataspace managers do not cooperate.

References [flags\(\)](#), and [size\(\)](#).

Referenced by [allocate\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:

**15.276.2.4 flags()**

```
Dataspace::Flags Dataspace::flags () const [noexcept]
```

Get flags of the dataspace.

**Return values**

$\geq 0$	Flags of the dataspace
$< 0$	IPC errors

**See also**

[L4Re::Dataspace::F::Flags](#)

Definition at line 112 of file [dataspace\\_impl.h](#).


References [L4Re::Dataspace::Stats::flags](#), and [info\(\)](#).

Referenced by [L4vbus::Vbus::assign\\_dma\\_domain\(\)](#), [L4vbus::Vbus::assign\\_dma\\_domain\(\)](#), [copy\\_in\(\)](#), [info\(\)](#), [map\(\)](#), and [map\\_region\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:

**15.276.2.5 info()**

```

14_ret_t L4Re::Dataspace::info (
    Stats * stats)

```

Get information on the dataspace.

**Parameters**

<code>out</code>	<code>stats</code>	Dataspace information
------------------	--------------------	-----------------------


**Return values**

<code>0</code>	Success
<code>&lt;0</code>	IPC errors


References [flags\(\)](#), [info\(\)](#), [L4\\_RPC](#), [L4\\_RPC\\_NF](#), [map\(\)](#), and [map\\_info\(\)](#).

Referenced by [flags\(\)](#), [info\(\)](#), and [size\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:

**15.276.2.6 map()**

```

l4_ret_t Dataspace::map (
    Dataspace::Offset offset,

```



```

Dataspace::Flags flags,
Dataspace::Map_addr local_addr,
Dataspace::Map_addr min_addr,
Dataspace::Map_addr max_addr,
L4::Cap< L4::Task > dst = L4::Cap<L4::Task>::Invalid) const [noexcept]

```

Request a flexpage mapping from the dataspace.

### Parameters

<i>offset</i>	Offset to start within dataspace
<i>flags</i>	<a href="#">Dataspace</a> flags, see <a href="#">L4Re::Dataspace::F::Flags</a> .
<i>local_addr</i>	Local address to map to.
<i>min_addr</i>	Defines start of receive window. (Rounded down to page size.)
<i>max_addr</i>	Defines end of receive window. (Rounded up to page size.)
<i>dst</i>	Optional destination task of the mapping. If invalid, the callers task is implicitly the destination.

### Return values

<i>L4_EOK</i>	Success
<i>-L4_ERANGE</i>	Invalid offset.
<i>-L4_EPERM</i>	Insufficient permission to map with requested rights.
<i>&lt;0</i>	IPC errors


The map call will attempt to map the largest possible flexpage that covers the given local address and still fits into the region defined by *min\_addr* and *max\_addr*. If the given region is invalid or does not overlap the local address, the smallest valid page size is used.

Definition at line 84 of file [dataspace\\_impl.h](#).


References [flags\(\)](#), and [L4\\_LOG2\\_PAGESIZE](#).

Referenced by [info\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 15.276.2.7 map\_info()

```

long L4Re::Dataspace::map_info (
    l4_addr_t * start_addr,
    l4_addr_t * end_addr) [inline]

```

Get mapping range of dataspace.

In case of a MMU-less system, the dataspace must be mapped at the correct address in the task because virtual and physical address must match. This method returns the start and end address of the physically contiguous buffer backing the dataspace.

On MMU-enabled system any page aligned address is permissible. On such systems the method is just a stub.

#### Parameters

out	<i>start_addr</i>	Start address of dataspace.
out	<i>end_addr</i>	End address (inclusive) of dataspace.


#### Return values

>0	Start/end address have been set and need to be obeyed.
0	No constraint of mapping address.
-L4_EPERM	Cannot infer mapping address. <a href="#">Dataspace</a> not mappable.
<0	IPC errors.

Definition at line 306 of file [dataspace](#).

Referenced by [info\(\)](#).

Here is the caller graph for this function:



### 15.276.2.8 map\_region()

```

l4_ret_t Dataspace::map_region (
    Dataspace::Offset offset,
    Dataspace::Flags flags,
    Dataspace::Map_addr min_addr,
    Dataspace::Map_addr max_addr,
    L4::Cap< L4::Task > dst = L4::Cap<L4::Task>::Invalid) const [noexcept]

```

Map a part of a dataspace into a local memory area.

#### Parameters

<i>offset</i>	Offset to start within dataspace.
<i>flags</i>	<a href="#">Dataspace</a> flags, see <a href="#">L4Re::Dataspace::F::Flags</a> .
<i>min_addr</i>	(Inclusive) start of the receive area.
<i>max_addr</i>	(Exclusive) end of receive area.
<i>dst</i>	Optional destination task of the mapping. If invalid, the callers task is implicitly the destination.

#### Return values

<i>L4_EOK</i>	Success
<i>-L4_ERANGE</i>	Invalid offset or receive area larger than the dataspace.
<i>-L4_EPERM</i>	Insufficient permission to map with requested rights.
<i>&lt;0</i>	IPC errors


This is a convenience function which maps flexpages consecutively into the given memory area in the local task. The area is expected to be filled completely. If the dataspace is not large enough to provide the mappings for the entire size of the area, then an error is returned. Mappings may or may not have been already established at that point.

*offset* and *min\_addr* are rounded down to the next [L4\\_PAGESIZE](#) boundary when necessary. *max\_addr* is rounded up to the page boundary. If the resulting maximum address is less or equal than the minimum address, then the function is a noop.

Definition at line 45 of file [dataspace\\_impl.h](#).

References [flags\(\)](#), [L4\\_LOG2\\_PAGESIZE](#), [L4\\_UNLIKELY](#), [L4::round\\_order\(\)](#), and [L4::trunc\\_order\(\)](#).

Here is the call graph for this function:



### 15.276.2.9 size()

```
Dataspace::Size Dataspace::size () const [noexcept]
```

Get size of a dataspace.

#### Returns


Size of the dataspace in bytes.

Definition at line 100 of file [dataspace\\_impl.h](#).


References [info\(\)](#), and [L4Re::Dataspace::Stats::size](#).

Referenced by [allocate\(\)](#), [clear\(\)](#), and [copy\\_in\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



The documentation for this class was generated from the following files:


- [l4/re/dataspace](#)
- [l4/re/impl/dataspace\\_impl.h](#)

## 15.277 L4Re::Dataspace::F Struct Reference

[Dataspace](#) flags definitions.

```
#include <dataspace>
```

Collaboration diagram for L4Re::Dataspace::F:



### Public Types

- enum { [Caching\\_shift](#) = 4 }
- enum [Flags](#) {
   
[R](#) = L4\_FPAGE\_RO , [Ro](#) = L4\_FPAGE\_RO , [RW](#) = L4\_FPAGE\_RW , [W](#) = L4\_FPAGE\_W ,
   
[X](#) = L4\_FPAGE\_X , [RX](#) = L4\_FPAGE\_RX , [RWX](#) = L4\_FPAGE\_RWX , [Rights\\_mask](#) = 0x0f ,
   
[Normal](#) = 0x00 , [Cacheable](#) = Normal , [Bufferable](#) = 0x10 , [Uncacheable](#) = 0x20 ,
   
[Caching\\_mask](#) = 0x30 }
   
*[Flags](#) for map operations.*

### 15.277.1 Detailed Description

[Dataspace](#) flags definitions.

Definition at line [57](#) of file [dataspace](#).

### 15.277.2 Member Enumeration Documentation

#### 15.277.2.1 anonymous enum

anonymous enum

#### Enumerator

Caching_shift	shift value for caching flags
---------------	-------------------------------

Definition at line [59](#) of file [dataspace](#).

### 15.277.2.2 Flags

enum [L4Re::Dataspace::F::Flags](#)

[Flags](#) for map operations.

A dataspace implementation must check the requested flags during the map and other operations against the dataspace rights.

#### Enumerator

R	Request read-only mapping.
Ro	Request read-only mapping.
RW	Request read-write mapping.
W	Request write-only mapping.
X	Request execute-only mapping.
RX	Request read-execute mapping.
RWX	Request read-write-execute mapping.
Rights_mask	All rights bits available for mappings.
Normal	Request normal (cached) memory mapping. This is the default if no other cache-related flag was specified.
Cacheable	Request normal memory mapping.
Bufferable	Request bufferable (write buffered) mappings.
Uncacheable	Request uncacheable memory mappings.
Caching_mask	Mask for caching flags.

Definition at line 70 of file [dataspace](#).

The documentation for this struct was generated from the following file:


- [l4/re/dataspace](#)

## 15.278 L4Re::Dataspace::Stats Struct Reference

Information about the dataspace.

```
#include <dataspace>
```

Collaboration diagram for L4Re::Dataspace::Stats:



## Data Fields

- Size **size**  
*size*
- Flags **flags**  
*flags*

### 15.278.1 Detailed Description

Information about the dataspace.

Definition at line 128 of file [dataspace](#).

The documentation for this struct was generated from the following file:


- [l4/re/dataspace](#)

## 15.279 L4Re::Debug\_obj Class Reference

Debug interface.


```
#include <debug>
```

Inheritance diagram for L4Re::Debug\_obj:





Collaboration diagram for L4Re::Debug\_obj:



## Public Member Functions

- [l4\\_ret\\_t debug](#) (unsigned long function)  
*Debug call.*

## Public Member Functions inherited from [L4::Kobject](#)

- [l4\\_msgtag\\_t dec\\_refcnt](#) ([l4\\_mword\\_t](#) diff, [l4\\_utcb\\_t](#) \*utcb=[l4\\_utcb\(\)](#))  
*Decrement the in kernel reference counter for the object.*

## Additional Inherited Members

## Protected Types inherited from

[L4::Kobject\\_t< Debug\\_obj, L4::Kobject, L4RE\\_PROTO\\_DEBUG >](#)

- typedef `Debug_obj` **Class**

*The target interface type (inheriting from [Kobject\\_t](#)).*

- typedef Typeid::Iface< PROTO, Debug\_obj > **\_\_Iface**

*The interface description for the derived class.*

- typedef Typeid::Merge\_list< Typeid::Iface\_list< [\\_\\_Iface](#) >, typename L4::Kobject::\_\_Iface\_list > **\_\_Iface\_list**

*The list of all RPC interfaces provided directly or through inheritance.*

### Protected Member Functions inherited from [L4::Kobject\\_t< Debug\\_obj, L4::Kobject, L4RE\\_PROTO\\_DEBUG >](#)

- [L4::Cap< Class > c](#) () const noexcept

*Get the capability to ourselves.*

### Protected Member Functions inherited from [L4::Kobject](#)

- [l4\\_cap\\_idx\\_t cap](#) () const noexcept

*Return capability selector.*

### Static Protected Member Functions inherited from [L4::Kobject\\_t< Debug\\_obj, L4::Kobject, L4RE\\_PROTO\\_DEBUG >](#)

- static void [\\_\\_check\\_protocols\\_\\_](#) () noexcept

*Helper to check for protocol conflicts.*

## 15.279.1 Detailed Description

Debug interface.

See also

[Debugging API](#) .

Definition at line 40 of file [debug](#).

## 15.279.2 Member Function Documentation

### 15.279.2.1 debug()

```
l4_ret_t L4Re::Debug_obj::debug (
    unsigned long function)
```

Debug call.

#### Parameters

<i>function</i>	Function to call.
-----------------	-------------------

**Returns**


- L4\_EOK
- IPC errors

An object can provide a number of debug functions, each identified by some integer. This method is used to fan out to these functions from a common entry point.


References [debug\(\)](#).

Referenced by [debug\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



The documentation for this class was generated from the following file:

- [l4/re/debug](#)

## 15.280 L4Re::Default\_event\_payload Struct Reference

Default event stream payload.

```
#include <event>
```

Collaboration diagram for L4Re::Default\_event\_payload:

L4Re::Default_event_payload
+ type
+ code
+ value
+ stream_id

#### Data Fields

- unsigned short **type**  
*Type of event.*
- unsigned short **code**  
*Code of event.*
- int **value**  
*Value of event.*
- [l4\\_umword\\_t](#) **stream\_id**  
*Stream ID.*

### 15.280.1 Detailed Description

Default event stream payload.

Definition at line [234](#) of file [event](#).

The documentation for this struct was generated from the following file:


- [l4/re/event](#)

## 15.281 L4Re::Dma\_space Class Reference

Managed DMA Address Space.

```
#include <dma_space>
```

Collaboration diagram for L4Re::Dma\_space:



## Public Types

- enum [Direction](#) { [Bidirectional](#) , [To\\_device](#) , [From\\_device](#) , [None](#) }  
*Direction of the DMA transfers.*
- enum [Attribute](#) { [No\\_sync](#) }  
*Attributes used for the memory region during the transfer.*
- enum [Space\\_attrib](#) { [Coherent](#) , [Phys\\_space](#) }  
*Attributes assigned to the DMA space when associated with a specific device.*
- typedef [l4\\_uint64\\_t](#) [Dma\\_addr](#)  
*Data type for DMA addresses.*
- typedef [L4::Types::Flags](#)< [Attribute](#) > [Attributes](#)  
*Attributes for DMA mappings.*
- typedef [L4::Types::Flags](#)< [Space\\_attrib](#) > [Space\\_attribs](#)  
*Attributes used when configuring the DMA space.*

## Public Member Functions

- [l4\\_ret\\_t](#) [map](#) ([L4::lpc::Cap](#)< [L4Re::Dataspace](#) > src, [L4Re::Dataspace::Offset](#) offset, [L4::lpc::In\\_out](#)< [l4\\_size\\_t](#) \* > size, [Attributes](#) attrs, [Direction](#) dir, [Dma\\_addr](#) \*dma\_addr)  
*Map the given part of this data space into the DMA address space.*
- [l4\\_ret\\_t](#) [unmap](#) ([Dma\\_addr](#) dma\_addr, [l4\\_size\\_t](#) size, [Attributes](#) attrs, [Direction](#) dir)  
*Unmap the given part of this data space from the DMA address space.*
- [l4\\_ret\\_t](#) [associate](#) ([L4::lpc::Opt](#)< [L4::lpc::Cap](#)< [L4::Task](#) > > dma\_task, [Space\\_attribs](#) attr)  
*Associate a (kernel) DMA space for a device to this DMA space.*
- [l4\\_ret\\_t](#) [disassociate](#) ()  
*Disassociate the (kernel) DMA space from this DMA space.*

### 15.281.1 Detailed Description

Managed DMA Address Space.

A managed [Dma\\_space](#) represents the [L4Re](#) abstraction of an DMA address space of one or several devices. Devices are assigned to a managed [Dma\\_space](#) by binding the [Dma\\_space](#) to the respective DMA domain (see [L4vbus::Vbus::assign\\_dma\\_domain\(\)](#)), which might link the [Dma\\_space](#) with a kernel [DMA space](#). Note that several DMA domains can be bound to the same [Dma\\_space](#). Whenever a device needs direct access to parts of an [L4Re::Dataspace](#), that part of the data space must be mapped to the managed [Dma\\_space](#) that is assigned to that device. Binding to DMA domains must happen before mapping. After the DMA accesses to the memory are finished the memory must be unmapped from the device's DMA address space.

Mapping to a managed DMA address space, using [map\(\)](#), makes the given parts of the data space visible to the associated device at the returned DMA address. As long as the memory is mapped into a DMA space it is 'pinned' and cannot be subject to dynamic memory management such as swapping. Additionally, [map\(\)](#) is responsible for the necessary syncing operations before the DMA.

[unmap\(\)](#) is the reverse operation to [map\(\)](#) and unmaps the given data-space part for the DMA address space. [unmap\(\)](#) is responsible for the necessary sync operations after the DMA.

Definition at line 52 of file [dma\\_space](#).

### 15.281.2 Member Typedef Documentation

#### 15.281.2.1 Attributes

```
typedef L4::Types::Flags<Attribute> L4Re::Dma_space::Attributes
```

[Attributes](#) for DMA mappings.

See also

[Attribute](#)

Definition at line 97 of file [dma\\_space](#).

### 15.281.3 Member Enumeration Documentation

#### 15.281.3.1 Attribute

```
enum L4Re::Dma_space::Attribute
```

[Attributes](#) used for the memory region during the transfer.

See also

[Attributes](#)

### Enumerator

No_sync	Do not sync the memory hierarchy. When this flag is <i>not set</i> (default) the memory region shall be made coherent to the point-of-coherency of the device associated with this <a href="#">Dma_space</a> . When using this attribute the client is responsible for syncing the memory hierarchy for DMA. This can either be done using the cache API or by another <a href="#">map()</a> or <a href="#">unmap()</a> operation of the same part of the data space (without the <a href="#">No_sync</a> attribute).
---------	---

Definition at line 76 of file [dma\\_space](#).

### 15.281.3.2 Direction

```
enum L4Re::Dma_space::Direction
```

[Direction](#) of the DMA transfers.

### Enumerator

Bidirectional	device reads and writes to the memory
To_device	device reads the memory
From_device	device writes to the memory
None	device is coherently connected to the memory

Definition at line 64 of file [dma\\_space](#).

### 15.281.3.3 Space\_attrb

```
enum L4Re::Dma_space::Space_attrb
```

[Attributes](#) assigned to the DMA space when associated with a specific device.

See also

[Space\\_attrbs](#)

### Enumerator

Coherent	The device is connected coherently with the cache. This means that the <a href="#">map()</a> and <a href="#">unmap()</a> do not need to sync CPU caches before and after DMA.
Phys_space	The DMA space has no DMA task assigned and uses the CPUs physical memory.

Definition at line 104 of file [dma\\_space](#).

## 15.281.4 Member Function Documentation

### 15.281.4.1 associate()

```
l4_ret_t L4Re::Dma_space::associate (
    L4::Ipc::Opt< L4::Ipc::Cap< L4::Task > > dma_task,
    Space_attribs attr)
```

Associate a (kernel) [DMA space](#) for a device to this [Dma\\_space](#).

#### Parameters

in	<i>dma_task</i>	The (kernel) <a href="#">DMA space</a> used for the device that shall be associated with this DMA space. In case no IOMMU is present or configured, the <i>dma_task</i> might be an invalid capability when <a href="#">L4Re::Dma_space::Phys_space</a> is set in <i>attr</i> , in this case the CPUs physical memory is used as DMA address space.
in	<i>attr</i>	<a href="#">Attributes</a> for this DMA space. See <a href="#">L4Re::Dma_space::Space_attrb</a> .

#### Return values

<i>L4_EOK</i>	Operation successful.
<i>-L4_EPERM</i>	Insufficient permissions; see precondition.
<i>-L4_EINVAL</i>	
<i>-L4_ENOENT</i>	

#### Precondition

The invoked [Dma\\_space](#) capability must have the permission [L4\\_CAP\\_FPAGE\\_W](#).


References [disassociate\(\)](#).

Referenced by [unmap\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:





### 15.281.4.2 disassociate()

```
l4_ret_t L4Re::Dma_space::disassociate ()
```

Disassociate the (kernel) [DMA space](#) from this [Dma\\_space](#).

#### Return values


<i>L4_EOK</i>	Operation successful.
<i>-L4_EPERM</i>	Insufficient permissions; see precondition.
<i>-L4_ENOENT</i>	

#### Precondition

The invoked [Dma\\_space](#) capability must have the permission [L4\\_CAP\\_FPAGE\\_W](#).

Referenced by [associate\(\)](#).

Here is the caller graph for this function:



### 15.281.4.3 map()

```
l4_ret_t L4Re::Dma_space::map (
    L4::Ipc::Cap< L4Re::Dataspace > src,
    L4Re::Dataspace::Offset offset,
    L4::Ipc::In_out< l4_size_t * > size,
    Attributes attrs,
    Direction dir,
    Dma_addr * dma_addr)
```

Map the given part of this data space into the DMA address space.

#### Parameters

in	<i>src</i>	Source data space (that describes the memory). Caller needs write right to the data space.
in	<i>offset</i>	The offset (bytes) within <i>src</i> .
in, out	<i>size</i>	The size (bytes) of the region to be mapped for DMA, after successful mapping the size returned is the size mapped for DMA as a single block. This size might be smaller than the original input size, in this case the caller might call <a href="#">map()</a> again with a new offset and the remaining size.
in	<i>attrs</i>	The attributes used for this DMA mapping (a combination of <a href="#">Dma_space::Attribute</a> values).

in	<i>dir</i>	The direction of the DMA transfer issued with this mapping. The same value must later be passed to <a href="#">unmap()</a> .
out	<i>dma_addr</i>	The DMA address to use for DMA with the associated device.

### Return values

<i>L4_EOK</i>	Operation successful.
<i>-L4_EPERM</i>	Insufficient permissions; see precondition.
<i>-L4_EINVAL</i>	The capability <i>src</i> is invalid or does not refer to a valid dataspace.
<i>-L4_EEXIST</i>	The specified region overlaps an existing mapping.
<i>-L4_ENOMEM</i>	Not enough memory to allocate internal datastructures.
<i>-L4_ERANGE</i>	<i>offset</i> is larger than the size of the dataspace.

### Precondition

The capability *src* must have the permission [L4\\_CAP\\_FPAGE\\_W](#).

### Note

[associate\(\)](#) must be called prior to mapping memory. Usually this is done implicitly when binding the managed [Dma\\_space](#) to a DMA domain (see [L4vbus::Vbus::assign\\_dma\\_domain\(\)](#)).

References [unmap\(\)](#).

Here is the call graph for this function:



#### 15.281.4.4 unmap()

```

l4_ret_t L4Re::Dma_space::unmap (
    Dma_addr dma_addr,
    l4_size_t size,
    Attributes attrs,
    Direction dir)
  
```

Unmap the given part of this data space from the DMA address space.

### Parameters

<i>dma_addr</i>	The DMA address (returned by <a href="#">Dma_space::map()</a> ).
<i>size</i>	The size (bytes) of the memory region to unmap.

<i>attrs</i>	The attributes for the unmap (currently none).
<i>dir</i>	The direction of the finished DMA operation.


#### Returns

0 in the case of success, a negative error code otherwise.

References [associate\(\)](#).

Referenced by [map\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



The documentation for this class was generated from the following file:


- [l4/re/dma\\_space](#)

## 15.282 L4Re::Env Class Reference

C++ interface of the initial environment that is provided to an [L4](#) task.

```
#include <env>
```

Collaboration diagram for L4Re::Env:



## Public Types

- typedef [l4re\\_env\\_cap\\_entry\\_t](#) **Cap\_entry**  
C++ type for an entry in the initial objects array.

## Public Member Functions

- [L4::Cap](#)< [Parent](#) > [parent](#) () const noexcept  
*Object-capability to the parent.*
- [L4::Cap](#)< [Mem\\_alloc](#) > [mem\\_alloc](#) () const noexcept  
*Object-capability to the memory allocator.*
- [L4::Cap](#)< [L4::Factory](#) > **user\_factory** () const noexcept  
*Object-capability to the user-level object factory.*
- [L4::Cap](#)< [Rm](#) > [rm](#) () const noexcept  
*Object-capability to the region map.*
- [L4::Cap](#)< [Log](#) > [log](#) () const noexcept  
*Object-capability to the logging service.*
- [L4::Cap](#)< [L4::Thread](#) > [main\\_thread](#) () const noexcept  
*Object-capability of the first user thread.*
- [L4::Cap](#)< [L4::Task](#) > [task](#) () const noexcept  
*Object-capability of the user task.*
- [L4::Cap](#)< [L4::Factory](#) > [factory](#) () const noexcept  
*Object-capability to the factory object available to the task.*

- [l4\\_cap\\_idx\\_t first\\_free\\_cap](#) () const noexcept  
*First available capability selector.*
- [l4\\_fpage\\_t utcb\\_area](#) () const noexcept  
*UTCB area of the task.*
- [l4\\_addr\\_t first\\_free\\_utcb](#) () const noexcept  
*First free UTCB.*
- [Cap\\_entry](#) const \* [initial\\_caps](#) () const noexcept  
*Get a pointer to the first entry in the initial objects array.*
- [Cap\\_entry](#) const \* [get](#) (char const \*name, unsigned l) const noexcept  
*Get the [Cap\\_entry](#) for the object named name.*
- template<typename T>  
[L4::Cap](#)< T > [get\\_cap](#) (char const \*name, unsigned l) const noexcept  
*Get the capability selector for the object named name.*
- template<typename T>  
[L4::Cap](#)< T > [get\\_cap](#) (char const \*name) const noexcept  
*Get the capability selector for the object named name.*
- void [parent](#) ([L4::Cap](#)< [Parent](#) > const &c) noexcept  
*Set parent object-capability.*
- void [mem\\_alloc](#) ([L4::Cap](#)< [Mem\\_alloc](#) > const &c) noexcept  
*Set memory allocator object-capability.*
- void [rm](#) ([L4::Cap](#)< [Rm](#) > const &c) noexcept  
*Set region map object-capability.*
- void [log](#) ([L4::Cap](#)< [Log](#) > const &c) noexcept  
*Set log object-capability.*
- void [main\\_thread](#) ([L4::Cap](#)< [L4::Thread](#) > const &c) noexcept  
*Set object-capability of first user thread.*
- void [factory](#) ([L4::Cap](#)< [L4::Factory](#) > const &c) noexcept  
*Set factory object-capability.*
- void [first\\_free\\_cap](#) ([l4\\_cap\\_idx\\_t](#) c) noexcept  
*Set first available capability selector.*
- void [utcb\\_area](#) ([l4\\_fpage\\_t](#) utcb) noexcept  
*Set UTCB area of the task.*
- void [first\\_free\\_utcb](#) ([l4\\_addr\\_t](#) u) noexcept  
*Set first free UTCB.*
- [L4::Cap](#)< [L4::Scheduler](#) > [scheduler](#) () const noexcept  
*Get the scheduler capability for the task.*
- void [scheduler](#) ([L4::Cap](#)< [L4::Scheduler](#) > const &c) noexcept  
*Set the scheduler capability.*
- [L4::Cap](#)< [Itas](#) > [itas](#) () const noexcept  
*Object-capability to the ITAS services.*
- void [itas](#) ([L4::Cap](#)< [Itas](#) > const &c) noexcept  
*Set the ITAS capability.*
- [L4::Cap](#)< [Dbg\\_events](#) > [dbg\\_events](#) () const noexcept  
*Object-capability to a debugger events service.*
- void [dbg\\_events](#) ([L4::Cap](#)< [Dbg\\_events](#) > const &dbg\_events) noexcept  
*Set the dbg\_events capability.*
- void [initial\\_caps](#) ([Cap\\_entry](#) \*first) noexcept  
*Set the pointer to the first [Cap\\_entry](#) in the initial objects array.*

## Static Public Member Functions

- static [Env](#) const \* [env](#) () noexcept  
*Returns the initial environment for the current task.*

### 15.282.1 Detailed Description

C++ interface of the initial environment that is provided to an [L4](#) task.

The initial environment is provided to each [L4](#) task that is started by an [L4Re](#) conform loader, such as the Moe root task. The initial environment provides access to a set of initial capabilities and some additional information about the available resources, such as free UTCBs (see [Virtual Registers](#) ) and available entries in capability table (provided by the micro kernel).

Each of the initial capabilities is stored at a fixed index in the task's capability table and the [L4](#) runtime environment provides convenience functions to retrieve the capabilities. See the table below for an comprehensive overview.

Name	Object Type	Convenience Function
parent	<a href="#">L4Re::Parent</a>	<a href="#">L4Re::Env::parent()</a>
user_factory	<a href="#">L4::Factory</a>	<a href="#">L4Re::Env::user_factory()</a>
log	<a href="#">L4Re::Log</a>	<a href="#">L4Re::Env::log()</a>
main_thread	<a href="#">L4::Thread</a>	<a href="#">L4Re::Env::main_thread()</a>
rm	<a href="#">L4Re::Rm</a>	<a href="#">L4Re::Env::rm()</a>
factory	<a href="#">L4::Factory</a>	<a href="#">L4Re::Env::factory()</a>
task	<a href="#">L4::Task</a>	<a href="#">L4Re::Env::task()</a>
scheduler	<a href="#">L4::Scheduler</a>	<a href="#">L4Re::Env::scheduler()</a>
itas	<a href="#">L4Re::Itas</a>	<a href="#">L4Re::Env::itas()</a>

Additional information found in the initial environment is:

- First free entry in capability table
- The [UTCB](#) area (as flexpage)
- First free UTCB (address in the UTCB area)

#### Include File

```
#include <l4/re/env>
```

For an explanation of the default task capabilities see [l4\\_default\\_caps\\_t](#).

For the C interface refer to [Initial Environment](#).

Definition at line 78 of file [env](#).

## 15.282.2 Member Function Documentation

### 15.282.2.1 dbg\_events() [1/2]

`L4::Cap< Dbg_events > L4Re::Env::dbg_events () const [inline], [noexcept]`

Object-capability to a debugger events service.

#### Returns

Dbg\_events object-capability

This capability can be invalid.

Definition at line 314 of file `env`.

Referenced by `dbg_events()`.

Here is the caller graph for this function:



### 15.282.2.2 dbg\_events() [2/2]

```

void L4Re::Env::dbg_events (
    L4::Cap< Dbg_events > const & dbg_events) [inline], [noexcept]
  
```

Set the dbg\_events capability.

#### Parameters

<code>dbg_events</code>	is the capability to be set for the debug events service.
-------------------------	---

Note that the capability can be invalid.

Definition at line 324 of file `env`.

References `dbg_events()`.

Here is the call graph for this function:



### 15.282.2.3 env()

```
Env const * L4Re::Env::env () [inline], [static], [noexcept]
```

Returns the initial environment for the current task.

#### Returns

Pointer to the initial environment class.

A typical use of this function is `L4Re::Env::env()-><member>()`


#### Examples

`examples/clntsrv/src/client.cc`, `examples/libs/l4re/c++/mem_alloc/ma+rm.cc`, `examples/libs/l4re/c++/shared_ds/ds_clnt.cc`, `examples/libs/l4re/c++/shared_ds/ds_srv.cc`, `examples/libs/l4re/streammap/client.cc`, and `examples/sys/migrate/thread_migrate.cc`

Definition at line 96 of file `env`.

Referenced by `L4virtio::Svr::Dev_config::Dev_config()`, `L4virtio::Driver::Device::driver_connect()`, `L4vcpu::Vcpu::ext_alloc()`, `L4Re::Util::Event_t< Default_event_payload >::init()`, `L4Re::Util::Event_t< Default_event_payload >::init_poll()`, `L4Re::Util::kumem_alloc()`, `L4virtio::Driver::Block_device::setup_device()`, and `L4virtio::Driver::Virtio_net_device::setup_device()`.

Here is the caller graph for this function:





#### 15.282.2.4 factory() [1/2]

```
L4::Cap< L4::Factory > L4Re::Env::factory () const [inline], [noexcept]
```

Object-capability to the factory object available to the task.

##### Returns

Factory object-capability

Definition at line 148 of file [env](#).

#### 15.282.2.5 factory() [2/2]

```
void L4Re::Env::factory (  
    L4::Cap< L4::Factory > const & c) [inline], [noexcept]
```

Set factory object-capability.

##### Parameters

<i>c</i>	Factory object-capability
----------	---------------------------

Definition at line 253 of file [env](#).

#### 15.282.2.6 first\_free\_cap() [1/2]

```
l4_cap_idx_t L4Re::Env::first_free_cap () const [inline], [noexcept]
```

First available capability selector.

##### Returns

First capability selector.

First capability selector available for use for in the application.

Definition at line 156 of file [env](#).

### 15.282.2.7 first\_free\_cap() [2/2]

```
void L4Re::Env::first_free_cap (
    l4_cap_idx_t c) [inline], [noexcept]
```

Set first available capability selector.

#### Parameters

<i>c</i>	First capability selector available to the application.
----------	---

Definition at line 259 of file [env](#).

### 15.282.2.8 first\_free\_utcb() [1/2]

```
l4_addr_t L4Re::Env::first_free_utcb () const [inline], [noexcept]
```

First free UTCB.

#### Returns

object-capability

First free UTCB within the UTCB area available for the application to use.

Definition at line 171 of file [env](#).

### 15.282.2.9 first\_free\_utcb() [2/2]

```
void L4Re::Env::first_free_utcb (
    l4_addr_t u) [inline], [noexcept]
```

Set first free UTCB.

#### Parameters

<i>u</i>	First UTCB available for the application to use.
----------	--

Definition at line 271 of file [env](#).

### 15.282.2.10 get()

```
Cap_entry const * L4Re::Env::get (
    char const * name,
    unsigned l) const [inline], [noexcept]
```

Get the [Cap\\_entry](#) for the object named *name*.

#### Parameters

<i>name</i>	is the name of the object.
<i>l</i>	is the length of the name, thus <i>name</i> might not be zero terminated.

#### Returns

A pointer to the [Cap\\_entry](#) for the object named *name*, or NULL if no such object was found.

Definition at line 189 of file [env](#).


References [l4re\\_env\\_get\\_cap\\_l\(\)](#).

Referenced by [get\\_cap\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



**15.282.2.11** `get_cap()` [1/2]

```
template<typename T>
L4::Cap< T > L4Re::Env::get_cap (
    char const * name) const [inline], [noexcept]
```

Get the capability selector for the object named *name*.

**Parameters**

<i>name</i>	is the name of the object (zero terminated).
-------------	--

**Returns**

A capability selector for the object named *name*, or an invalid capability selector if no such object was found.

Definition at line 216 of file `env`.

References `get_cap()`.

Here is the call graph for this function:

**15.282.2.12** `get_cap()` [2/2]

```
template<typename T>
L4::Cap< T > L4Re::Env::get_cap (
    char const * name,
    unsigned l) const [inline], [noexcept]
```

Get the capability selector for the object named *name*.

**Parameters**

<i>name</i>	is the name of the object.
<i>l</i>	is the length of the name, thus <i>name</i> might not be zero terminated.

**Returns**

A capability selector for the object named *name*, or an invalid capability selector if no such object was found.

**Examples**


[examples/clntsrv/src/client.cc](#), [examples/libs/l4re/c++/shared\\_ds/ds\\_clnt.cc](#), and [examples/libs/l4re/streammap/client.cc](#).

Definition at line 201 of file [env](#).

References [get\(\)](#), and [L4\\_ENOENT](#).

Referenced by [get\\_cap\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:

**15.282.2.13 initial\_caps() [1/2]**

```
Cap_entry const * L4Re::Env::initial_caps () const [inline], [noexcept]
```

Get a pointer to the first entry in the initial objects array.

**Returns**

A pointer to the first entry in the initial objects array.

Definition at line 178 of file [env](#).

**15.282.2.14 initial\_caps()** [2/2]

```
void L4Re::Env::initial_caps (
    Cap_entry * first) [inline], [noexcept]
```

Set the pointer to the first [Cap\\_entry](#) in the initial objects array.

**Parameters**

<i>first</i>	is the first element in the array.
--------------	------------------------------------

Definition at line [331](#) of file [env](#).

**15.282.2.15 itas()** [1/2]

```
L4::Cap< Itas > L4Re::Env::itas () const [inline], [noexcept]
```

Object-capability to the ITAS services.

**Returns**

ITAS object-capability

Attention: this capability might be invalid, depending on the system configuration. Regular applications must not use it directly as it is an implementation detail of the [L4Re](#) libc that is subject to change without notice!

Definition at line [298](#) of file [env](#).

**15.282.2.16 itas()** [2/2]

```
void L4Re::Env::itas (
    L4::Cap< Itas > const & c) [inline], [noexcept]
```

Set the ITAS capability.

**Parameters**

<i>c</i>	is the capability to be set as ITAS.
----------	--------------------------------------

Definition at line [305](#) of file [env](#).

**15.282.2.17 log()** [1/2]

```
L4::Cap< Log > L4Re::Env::log () const [inline], [noexcept]
```

Object-capability to the logging service.

Might be invalid if there is no logging service available to the application!

**Returns**

[Log](#) object-capability

Definition at line [130](#) of file [env](#).

**15.282.2.18 log()** [2/2]

```
void L4Re::Env::log (
    L4::Cap< Log > const & c) [inline], [noexcept]
```

Set log object-capability.

**Parameters**

<code>c</code>	Log object-capability
----------------	-----------------------

Definition at line 241 of file [env](#).

**15.282.2.19 main\_thread()** [1/2]

```
L4::Cap< L4::Thread > L4Re::Env::main_thread () const [inline], [noexcept]
```

Object-capability of the first user thread.

**Returns**

Object-capability of the first user thread.

Definition at line 136 of file [env](#).

**15.282.2.20 main\_thread()** [2/2]

```
void L4Re::Env::main_thread (
    L4::Cap< L4::Thread > const & c) [inline], [noexcept]
```

Set object-capability of first user thread.

**Parameters**

<code>c</code>	First thread's object-capability
----------------	----------------------------------

Definition at line 247 of file [env](#).

**15.282.2.21 mem\_alloc()** [1/2]

```
L4::Cap< Mem_alloc > L4Re::Env::mem_alloc () const [inline], [noexcept]
```

Object-capability to the memory allocator.

**Returns**

Memory allocator object-capability

**Examples**

[examples/libs/l4re/c++/shared\\_ds/ds\\_srv.cc](#).

Definition at line 109 of file [env](#).

**15.282.2.22 mem\_alloc()** [2/2]

```
void L4Re::Env::mem_alloc (
    L4::Cap< Mem_alloc > const & c) [inline], [noexcept]
```

Set memory allocator object-capability.

**Parameters**

<i>c</i>	Memory allocator object-capability
----------	------------------------------------

Definition at line 229 of file [env](#).

**15.282.2.23 parent()** [1/2]

```
L4::Cap< Parent > L4Re::Env::parent () const [inline], [noexcept]
```

Object-capability to the parent.

**Returns**

[Parent](#) object-capability

Definition at line 103 of file [env](#).

**15.282.2.24 parent()** [2/2]

```
void L4Re::Env::parent (
    L4::Cap< Parent > const & c) [inline], [noexcept]
```

Set parent object-capability.

**Parameters**

<i>c</i>	<a href="#">Parent</a> object-capability
----------	--

Definition at line 223 of file [env](#).

**15.282.2.25 rm()** [1/2]

```
L4::Cap< Rm > L4Re::Env::rm () const [inline], [noexcept]
```

Object-capability to the region map.

**Returns**

Region map object-capability

**Examples**

[examples/libs/l4re/c++/shared\\_ds/ds\\_clnt.cc](#), and [examples/libs/l4re/c++/shared\\_ds/ds\\_srv.cc](#).

Definition at line 120 of file [env](#).



**15.282.2.26 rm()** [2/2]

```
void L4Re::Env::rm (
    L4::Cap< Rm > const & c) [inline], [noexcept]
```

Set region map object-capability.

**Parameters**

c	Region map object-capability
---	------------------------------

Definition at line 235 of file [env](#).

**15.282.2.27 scheduler()** [1/2]

```
L4::Cap< L4::Scheduler > L4Re::Env::scheduler () const [inline], [noexcept]
```

Get the scheduler capability for the task.

**Returns**

The capability selector for the default scheduler used for this task.

Definition at line 279 of file [env](#).

**15.282.2.28 scheduler()** [2/2]

```
void L4Re::Env::scheduler (
    L4::Cap< L4::Scheduler > const & c) [inline], [noexcept]
```

Set the scheduler capability.

**Parameters**

c	is the capability to be set as scheduler.
---	---

Definition at line 286 of file [env](#).

**15.282.2.29 task()**

```
L4::Cap< L4::Task > L4Re::Env::task () const [inline], [noexcept]
```

Object-capability of the user task.

**Returns**

Object-capability of the user task.

Definition at line 142 of file [env](#).

**15.282.2.30 utcb\_area()** [1/2]

```
l4_fpage_t L4Re::Env::utcb_area () const [inline], [noexcept]
```

UTCB area of the task.

**Returns**

UTCB area

Definition at line [162](#) of file [env](#).

**15.282.2.31 utcb\_area()** [2/2]

```
void L4Re::Env::utcb_area (
    l4_fpage_t utcbs) [inline], [noexcept]
```

Set UTCB area of the task.

**Parameters**

<i>utcbs</i>	UTCB area
--------------	-----------

Definition at line [265](#) of file [env](#).

The documentation for this class was generated from the following file:


- [l4/re/env](#)

**15.283 L4Re::Event Class Reference**


[Event](#) class.

```
#include <event>
```

Inheritance diagram for L4Re::Event:



Collaboration diagram for L4Re::Event:



## Public Member Functions

- `l4_ret_t get_buffer (L4::lpc::Out< L4::Cap< Dataspace > > ds)`  
Get event signal buffer.
- `l4_ret_t get_num_streams ()`  
Get number of event streams.
- `l4_ret_t get_stream_info (int idx, Event_stream_info *info)`

*Get event stream infos.*

- [l4\\_ret\\_t get\\_stream\\_info\\_for\\_id](#) ([l4\\_umword\\_t](#) stream\_id, [Event\\_stream\\_info](#) \*info)

*Get event stream infos.*

- [l4\\_ret\\_t get\\_axis\\_info](#) ([l4\\_umword\\_t](#) stream\_id, unsigned naxes, unsigned const \*axis, [Event\\_absinfo](#) \*info) const noexcept

*Get event stream axis infos.*

- [l4\\_ret\\_t get\\_stream\\_state\\_for\\_id](#) ([l4\\_umword\\_t](#) stream\_id, [Event\\_stream\\_state](#) \*state)

*Get event stream state.*

## Public Member Functions inherited from [L4::lcu](#)

- [l4\\_msgtag\\_t bind](#) (unsigned irqnum, [L4::Cap](#)< [Triggerable](#) > irq, [l4\\_utcb\\_t](#) \*utcb=[l4\\_utcb](#)()) noexcept

*Bind an interrupt line of an interrupt controller to an interrupt object.*

- [l4\\_msgtag\\_t unbind](#) (unsigned irqnum, [L4::Cap](#)< [Triggerable](#) > irq, [l4\\_utcb\\_t](#) \*utcb=[l4\\_utcb](#)()) noexcept

*Remove binding of an interrupt line from the interrupt controller object.*

- [l4\\_msgtag\\_t info](#) ([l4\\_icu\\_info\\_t](#) \*info, [l4\\_utcb\\_t](#) \*utcb=[l4\\_utcb](#)()) noexcept

*Get information about the ICU features.*

- [l4\\_msgtag\\_t msi\\_info](#) ([l4\\_umword\\_t](#) irqnum, [l4\\_uint64\\_t](#) source, [l4\\_icu\\_msi\\_info\\_t](#) \*msi\_info)

*Get MSI info about IRQ.*

- [l4\\_msgtag\\_t mask](#) (unsigned irqnum, [l4\\_umword\\_t](#) \*label=0, [l4\\_timeout\\_t](#) to=[L4\\_IPC\\_NEVER](#), [l4\\_utcb\\_t](#) \*utcb=[l4\\_utcb](#)()) noexcept

*Mask an IRQ line.*

- [l4\\_msgtag\\_t set\\_mode](#) (unsigned irqnum, [l4\\_umword\\_t](#) mode, [l4\\_utcb\\_t](#) \*utcb=[l4\\_utcb](#)()) noexcept

*Set interrupt mode.*

## Public Member Functions inherited from [L4::lrq\\_eoi](#)

- [l4\\_msgtag\\_t unmask](#) (unsigned irqnum, [l4\\_umword\\_t](#) \*label=0, [l4\\_timeout\\_t](#) to=[L4\\_IPC\\_NEVER](#), [l4\\_utcb\\_t](#) \*utcb=[l4\\_utcb](#)()) noexcept

*Unmask the given interrupt line.*

## Additional Inherited Members

## Protected Types inherited from [L4::Kobject\\_t](#)< [Event](#), [L4::lcu](#), [L4RE\\_PROTO\\_EVENT](#) >

- typedef [Event](#) **Class**  
*The target interface type (inheriting from [Kobject\\_t](#)).*
- typedef [Typeid::Iface](#)< [PROTO](#), [Event](#) > **\_\_Iface**  
*The interface description for the derived class.*
- typedef [Typeid::Merge\\_list](#)< [Typeid::Iface\\_list](#)< **\_\_Iface** >, typename [L4::lcu::\\_\\_Iface\\_list](#) > **\_\_Iface\_list**  
*The list of all RPC interfaces provided directly or through inheritance.*

## Protected Types inherited from

## [L4::Kobject\\_t](#)< [lcu](#), [lrq\\_eoi](#), [L4\\_PROTO\\_IRQ](#), [Type\\_info::Demand\\_t](#)< 1 > >

- typedef [lcu](#) **Class**  
*The target interface type (inheriting from [Kobject\\_t](#)).*
- typedef [Typeid::Iface](#)< [PROTO](#), [lcu](#) > **\_\_Iface**  
*The interface description for the derived class.*
- typedef [Typeid::Merge\\_list](#)< [Typeid::Iface\\_list](#)< **\_\_Iface** >, typename [lrq\\_eoi::\\_\\_Iface\\_list](#) > **\_\_Iface\_list**  
*The list of all RPC interfaces provided directly or through inheritance.*

### Protected Member Functions inherited from [L4::Kobject\\_t< Event, L4::lcu, L4RE\\_PROTO\\_EVENT >](#)

- [L4::Cap< Class > c \(\)](#) const noexcept  
*Get the capability to ourselves.*

### Protected Member Functions inherited from [L4::Kobject\\_t< lcu, Irq\\_eoi, L4\\_PROTO\\_IRQ, Type\\_info::Demand\\_t< 1 > >](#)

- [L4::Cap< Class > c \(\)](#) const noexcept  
*Get the capability to ourselves.*

### Static Protected Member Functions inherited from [L4::Kobject\\_t< Event, L4::lcu, L4RE\\_PROTO\\_EVENT >](#)

- static void [\\_\\_check\\_protocols\\_\\_ \(\)](#) noexcept  
*Helper to check for protocol conflicts.*

### Static Protected Member Functions inherited from [L4::Kobject\\_t< lcu, Irq\\_eoi, L4\\_PROTO\\_IRQ, Type\\_info::Demand\\_t< 1 > >](#)

- static void [\\_\\_check\\_protocols\\_\\_ \(\)](#) noexcept  
*Helper to check for protocol conflicts.*

## 15.283.1 Detailed Description

[Event](#) class.

See also

[L4Re Event API](#)

Definition at line 137 of file [event](#).

## 15.283.2 Member Function Documentation

### 15.283.2.1 [get\\_axis\\_info\(\)](#)

```
l4_ret_t L4Re::Event::get_axis_info (
    l4_umword_t stream_id,
    unsigned naxes,
    unsigned const * axis,
    Event_absinfo * info) const [inline], [noexcept]
```

Get event stream axis infos.

**Parameters**

	<i>stream</i> ↔ <i>_id</i>	ID of the event stream.
in	<i>naxes</i>	Number of axis IDs and axis infos.
in	<i>axis</i>	Array of axis IDs.
out	<i>info</i>	Array of axis infos.

**Return values**


$\geq 0$	Number of returned axes infos.
$< 0$	Error code.

Definition at line 200 of file [event](#).


References [L4::Kobject\\_t< Event, L4::lcu, L4RE\\_PROTO\\_EVENT >::c\(\)](#), and [L4::lcu::info\(\)](#).

Referenced by [get\\_stream\\_info\\_for\\_id\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 15.283.2.2 `get_buffer()`

```
l4_ret_t L4Re::Event::get_buffer (
    L4::Ipc::Out< L4::Cap< Dataspace > > ds)
```

Get event signal buffer.

#### Parameters

out	ds	Event buffer.
-----	----	---------------

#### Return values

0	Success
<0	Error

References [get\\_buffer\(\)](#).

Referenced by [get\\_buffer\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:





### 15.283.2.3 `get_num_streams()`

```
l4_ret_t L4Re::Event::get_num_streams ()
```

Get number of event streams.


#### Return values

$\geq 0$	Number of streams.
$< 0$	Error code.


References [get\\_num\\_streams\(\)](#).

Referenced by [get\\_num\\_streams\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 15.283.2.4 `get_stream_info()`

```
l4_ret_t L4Re::Event::get_stream_info (  
    int idx,  
    Event_stream_info * info)
```

Get event stream infos.

Deprecated. Use [get\\_stream\\_info\\_for\\_id\(\)](#).

#### Parameters

	<i>idx</i>	ID of the event stream.
out	<i>info</i>	<a href="#">Event</a> stream info.


#### Return values

0	Success
<0	Error


References [get\\_stream\\_info\(\)](#), and [L4::lcu::info\(\)](#).

Referenced by [get\\_stream\\_info\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



#### 15.283.2.5 get\_stream\_info\_for\_id()

```

l4_ret_t L4Re::Event::get_stream_info_for_id (
    l4_umword_t stream_id,
    Event_stream_info * info)

```

Get event stream infos.

**Parameters**

	<i>stream</i> ↔ <i>_id</i>	ID of the event stream.
out	<i>info</i>	<a href="#">Event</a> stream info.


**Return values**

0	Success
<0	Error


References [get\\_axis\\_info\(\)](#), [get\\_stream\\_info\\_for\\_id\(\)](#), and [L4::lcu::info\(\)](#).

Referenced by [get\\_stream\\_info\\_for\\_id\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:

**15.283.2.6 get\_stream\_state\_for\_id()**

```

l4_ret_t L4Re::Event::get_stream_state_for_id (
    l4_umword_t stream_id,
    Event_stream_state * state)

```

Get event stream state.

**Parameters**

	<i>stream</i> ↔ <i>_id</i>	ID of the event stream.
out	<i>state</i>	<a href="#">Event</a> stream state.

**Return values**

0	Success
<0	Error

The documentation for this class was generated from the following file:


- l4/re/event

## 15.284 L4Re::Event\_buffer\_t< PAYLOAD > Class Template Reference


[Event](#) buffer class.

```
#include <event>
```

Inheritance diagram for L4Re::Event\_buffer\_t< PAYLOAD >:



Collaboration diagram for L4Re::Event\_buffer\_t< PAYLOAD >:



## Data Structures

- struct [Event](#)  
*[Event](#) structure used in buffer.*

## Public Member Functions

- [Event\\_buffer\\_t](#) (void \*buffer, [l4\\_addr\\_t](#) size)  
*Initialize event buffer.*
- Event \* [next](#) () noexcept  
*Next event in buffer.*
- bool [put](#) (Event const &ev) noexcept  
*Put event into buffer at current position.*

### 15.284.1 Detailed Description

```
template<typename PAYLOAD = Default_event_payload>
class L4Re::Event_buffer_t< PAYLOAD >
```

[Event](#) buffer class.

Definition at line [248](#) of file [event](#).

## 15.284.2 Constructor & Destructor Documentation

### 15.284.2.1 Event\_buffer\_t()

```
template<typename PAYLOAD = Default_event_payload>
L4Re::Event_buffer_t< PAYLOAD >::Event_buffer_t (
    void * buffer,
    l4_addr_t size) [inline]
```

Initialize event buffer.

#### Parameters

<i>buffer</i>	Pointer to buffer.
<i>size</i>	Size of buffer in bytes.

Definition at line 295 of file [event](#).

## 15.284.3 Member Function Documentation

### 15.284.3.1 next()

```
template<typename PAYLOAD = Default_event_payload>
Event * L4Re::Event_buffer_t< PAYLOAD >::next () [inline], [noexcept]
```

Next event in buffer.

#### Returns

0 if no event available, event otherwise.

Definition at line 305 of file [event](#).

### 15.284.3.2 put()

```
template<typename PAYLOAD = Default_event_payload>
bool L4Re::Event_buffer_t< PAYLOAD >::put (
    Event const & ev) [inline], [noexcept]
```

Put event into buffer at current position.

#### Parameters

<i>ev</i>	<a href="#">Event</a> to put into the buffer.
-----------	---

#### Returns

false if buffer is full and entry could not be added.

Definition at line 322 of file [event](#).

The documentation for this class was generated from the following file:

- [l4/re/event](#)

## 15.285 L4Re::Event\_buffer\_t< PAYLOAD >::Event Struct Reference

[Event](#) structure used in buffer.

```
#include <event>
```

Collaboration diagram for L4Re::Event\_buffer\_t< PAYLOAD >::Event:

L4Re::Event_buffer _t< PAYLOAD >::Event	
+	time
+	free()

### Public Member Functions

- void **free** () noexcept  
*Free the entry.*

### Data Fields

- long long **time**  
*[Event](#) time stamp.*

### 15.285.1 Detailed Description

```
template<typename PAYLOAD = Default_event_payload>
struct L4Re::Event_buffer_t< PAYLOAD >::Event
```

[Event](#) structure used in buffer.

Definition at line 255 of file [event](#).

The documentation for this struct was generated from the following file:

- l4/re/event




## 15.286 L4Re::Inhibitor Class Reference


Set of inhibitor locks, which inhibit specific actions when held.

```
#include <inhibitor>
```

Inheritance diagram for L4Re::Inhibitor:



Collaboration diagram for L4Re::Inhibitor:



## Public Types

- enum { `Name_max` = 20 }

## Public Member Functions

- `l4_ret_t acquire (l4_umword_t id, L4::lpc::String<> reason)`  
*Acquire a specific inhibitor lock.*
- `l4_ret_t release (l4_umword_t id)`  
*Release a specific inhibitor lock.*
- `l4_ret_t next_lock_info (char *name, unsigned len, l4_mword_t current_id=-1, l4_utcb_t *utcb=l4_utcb())`  
*Get information for the next available inhibitor lock.*

## Public Member Functions inherited from [L4::Kobject](#)

- [l4\\_msgtag\\_t dec\\_refcnt](#) ([l4\\_mword\\_t diff](#), [l4\\_utcb\\_t \\*utcb=l4\\_utcb\(\)](#))

*Decrement the in kernel reference counter for the object.*

## Additional Inherited Members

## Protected Types inherited from

[L4::Kobject\\_t< Inhibitor, L4::Kobject, L4RE\\_PROTO\\_INHIBITOR >](#)

- typedef Inhibitor **Class**  
*The target interface type (inheriting from [Kobject\\_t](#)).*
- typedef Typeid::Iface< PROTO, Inhibitor > **\_\_iface**  
*The interface description for the derived class.*
- typedef Typeid::Merge\_list< Typeid::Iface\_list< **\_\_iface** >, typename L4::Kobject::\_\_iface\_list > **\_\_iface\_list**  
*The list of all RPC interfaces provided directly or through inheritance.*

## Protected Member Functions inherited from

[L4::Kobject\\_t< Inhibitor, L4::Kobject, L4RE\\_PROTO\\_INHIBITOR >](#)

- [L4::Cap< Class > c](#) () const noexcept

*Get the capability to ourselves.*

## Protected Member Functions inherited from [L4::Kobject](#)

- [l4\\_cap\\_idx\\_t cap](#) () const noexcept

*Return capability selector.*

## Static Protected Member Functions inherited from

[L4::Kobject\\_t< Inhibitor, L4::Kobject, L4RE\\_PROTO\\_INHIBITOR >](#)

- static void **\_\_check\_protocols\_\_** () noexcept

*Helper to check for protocol conflicts.*

### 15.286.1 Detailed Description

Set of inhibitor locks, which inhibit specific actions when held.

This interface provides access to a set of inhibitor locks, each determined by an ID that is specific to the [Inhibitor](#) object. Each individual lock shall prevent, a specific (implementation defined) action to be executed, as long as the lock is held.

For example there can be an inhibitor lock to prevent a transition to suspend-to-RAM state and a different one to prevent shutdown.

A client shall take an inhibitor lock if it needs to execute code before the action is taken. For example a lock-screen application shall grab an inhibitor lock for the suspend action to be able to lock the screen before the system goes to sleep.

[Inhibitor](#) locks are usually closely related to specific events. Usually a server automatically subscribes a client holding a lock to the corresponding event. The server shall send the event to inform the client that an action is pending. Upon reception of the event, the client is supposed to release the corresponding inhibitor lock.

Definition at line 38 of file [inhibitor](#).

## 15.286.2 Member Enumeration Documentation

### 15.286.2.1 anonymous enum

anonymous enum

#### Enumerator

Name_max	The maximum length of a lock's name.
----------	--------------------------------------

Definition at line 42 of file [inhibitor](#).

## 15.286.3 Member Function Documentation

### 15.286.3.1 acquire()

```
l4_ret_t L4Re::Inhibitor::acquire (
    l4_umword_t id,
    L4::Ipc::String<> reason)
```

Acquire a specific inhibitor lock.

#### Parameters

<i>id</i>	ID of the inhibitor lock that the client intends to acquire
<i>reason</i>	The reason why you need the lock. Used for informing the user or debugging.

#### Return values

0	Success
-L4_ENODEV	The specified <i>id</i> does not exist.


References [acquire\(\)](#).

Referenced by [acquire\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 15.286.3.2 next\_lock\_info()

```

l4_ret_t L4Re::Inhibitor::next_lock_info (
    char * name,
    unsigned len,
    l4_mword_t current_id = -1,
    l4_utcb_t * utcb = l4_utcb()) [inline]
  
```

Get information for the next available inhibitor lock.

#### Parameters

<i>name</i>	A pointer to a buffer for the name of the lock.
<i>len</i>	The length of the available buffer (usually <code>Name_max</code> is used).
<i>current_id</i>	The ID of the last available lock, use -1 to get the first lock.
<i>utcb</i>	The UTCB to use for the message.


#### Return values

<code>&gt;0</code>	The ID of the next available lock if there is one (in this case <code>name</code> shall contain the name of the inhibitor lock).
<code>-L4_ENODEV</code>	There are no more locks.

Definition at line 84 of file `inhibitor`.

References `L4::Kobject_t< Inhibitor, L4::Kobject, L4RE_PROTO_INHIBITOR >::c()`.

Here is the call graph for this function:



### 15.286.3.3 `release()`

```
l4_ret_t L4Re::Inhibitor::release (  
    l4_umword_t id)
```

Release a specific inhibitor lock.

#### Parameters

<i>id</i>	The ID of the inhibitor lock to release.
-----------	--


#### Return values

<i>0</i>	Success
<i>-L4_ENODEV</i>	Lock with the given <i>id</i> does not exist.


References [release\(\)](#).

Referenced by [release\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



The documentation for this class was generated from the following file:


- `l4/re/inhibitor`

## 15.287 L4Re::Itas Class Reference


Interface to the ITAS.

```
#include <itas>
```

Inheritance diagram for L4Re::Itas:



Collaboration diagram for L4Re::Itas:



## Public Types

- enum : unsigned { `ignore_sigaction` = ~0U }

## Public Member Functions

- int `register_thread` (L4::lpc::Cap< L4::Thread > parent, L4::lpc::Cap< L4::Thread > thread\_cap, l4\_addr\_t thread\_utcb)



- *Register new thread.*
- `int unregister_thread (L4::lpc::Cap< L4::Thread > thread)`
- *Unregister a thread.*
- `int sigaction (int signum, const struct sigaction *act, struct sigaction *oldact)`
- *Examine and change a POSIX signal action.*
- `int sigaltstack (L4::lpc::Cap< L4::Thread > thread, const struct sigaltstack *ss, struct sigaltstack *oss)`
- *Examine or set alternate POSIX signal stack.*
- `int sigprocmask (L4::lpc::Cap< L4::Thread > thread, int how, sigset_t const *set, sigset_t *oldset)`
- *Examine or set process signal mask.*
- `int sigpending (L4::lpc::Cap< L4::Thread > thread, sigset_t *set)`
- *Query pending signals.*
- `int setitimer (int which, const struct itimerval *new_value, struct itimerval *old_value)`
- *Set process interval timer.*
- `int getitimer (int which, struct itimerval *curr_value)`
- *Get process interval timer.*
- `int raise (L4::lpc::Cap< L4::Thread > thread, int sig)`
- *Send a signal to the calling thread.*

## Public Member Functions inherited from L4::Kobject

- `l4_msgtag_t dec_refcnt (l4_mword_t diff, l4_utcb_t *utcb=l4_utcb())`
- *Decrement the in kernel reference counter for the object.*

## Additional Inherited Members

## Protected Types inherited from

**L4::Kobject\_t< Itas, L4::Kobject, L4RE\_PROTO\_ITAS, L4::Type\_info::Demand\_t< 2 > >**

- `typedef Itas Class`
- *The target interface type (inheriting from [Kobject\\_t](#)).*
- `typedef Typeid::Iface< PROTO, Itas > __iface`
- *The interface description for the derived class.*
- `typedef Typeid::Merge_list< Typeid::Iface_list< __iface >, typename L4::Kobject::__iface_list > __iface_list`
- *The list of all RPC interfaces provided directly or through inheritance.*

## Protected Member Functions inherited from

**L4::Kobject\_t< Itas, L4::Kobject, L4RE\_PROTO\_ITAS, L4::Type\_info::Demand\_t< 2 > >**

- `L4::Cap< Class > c () const noexcept`
- *Get the capability to ourselves.*

## Protected Member Functions inherited from L4::Kobject

- `l4_cap_idx_t cap () const noexcept`
- *Return capability selector.*

## Static Protected Member Functions inherited from

[L4::Kobject\\_t< Itas, L4::Kobject, L4RE\\_PROTO\\_ITAS, L4::Type\\_info::Demand\\_t< 2 > >](#)

- static void `__check_protocols__()` noexcept  
*Helper to check for protocol conflicts.*

### 15.287.1 Detailed Description

Interface to the ITAS.

This is an internal interface between libc and the `l4re_itas`. Do not use it. It is subject to change.

Definition at line 30 of file [itas](#).

### 15.287.2 Member Enumeration Documentation

#### 15.287.2.1 anonymous enum

anonymous enum : unsigned

#### Enumerator

Ignore_sigaction	Ignore new action of <a href="#">sigaction()</a> call.
------------------	--

Definition at line 63 of file [itas](#).

### 15.287.3 Member Function Documentation

#### 15.287.3.1 getitimer()

```
int L4Re::Itas::getitimer (
    int which,
    struct itimerval * curr_value)
```

Get process interval timer.

See IEEE Std 1003.1-2017 [getitimer\(\)](#) for details.

#### Parameters

in	<i>which</i>	Timer type (ITIMER_REAL).
out	<i>curr_value</i>	Old timer value.

References [getitimer\(\)](#).

Referenced by [getitimer\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 15.287.3.2 raise()

```
int L4Re::Itas::raise (
    L4::Ipc::Cap< L4::Thread > thread,
    int sig)
```

Send a signal to the calling thread.

#### Parameters

in	<i>thread</i>	Thread cap of the calling thread.
in	<i>sig</i>	Signal that shall be raised.

References [raise\(\)](#).

Referenced by [raise\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 15.287.3.3 register\_thread()

```
int L4Re::Itas::register_thread (
    L4::Ipc::Cap< L4::Thread > parent,
    L4::Ipc::Cap< L4::Thread > thread_cap,
    l4_addr_t thread_utcb)
```

Register new thread.

Makes the newly created thread known to ITAS. The ITAS will do the `thread_cap->control()` to bind the thread to the task and attach the gates for pager and exception handler.

#### Parameters

<i>parent</i>	The capability of the thread that created the new thread.
<i>thread_cap</i>	The capability of the new thread.
<i>thread_utcb</i>	The address of the allocated UTCB of the new thread.

### 15.287.3.4 setitimer()

```
int L4Re::Itas::setitimer (
    int which,
    const struct itimerval * new_value,
    struct itimerval * old_value)
```

Set process interval timer.

See IEEE Std 1003.1-2017 [setitimer\(\)](#) for details.

#### Parameters

in	<i>which</i>	Timer type (ITIMER_REAL).
in	<i>new_value</i>	New timer value.
out	<i>old_value</i>	Old timer value.

Referenced by [sigpending\(\)](#).

Here is the caller graph for this function:



### 15.287.3.5 sigaction()

```

int L4Re::Itas::sigaction (
    int signum,
    const struct sigaction * act,
    struct sigaction * oldact)

```

Examine and change a POSIX signal action.

See IEEE Std 1003.1-2024 [sigaction\(\)](#) for the behaviour of the method.

If `act->sa_flags` is [Ignore\\_sigaction](#), the new action is ignored.

#### Parameters

in	<i>signum</i>	Signal number to be examined and/or modified.
in	<i>act</i>	New signal action.
out	<i>oldact</i>	Old signal action.


References [sigaction\(\)](#), and [sigaltstack\(\)](#).

Referenced by [sigaction\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 15.287.3.6 sigaltstack()

```
int L4Re::Itas::sigaltstack (
    L4::Ipc::Cap< L4::Thread > thread,
    const struct sigaltstack * ss,
    struct sigaltstack * oss)
```

Examine or set alternate POSIX signal stack.

See IEEE Std 1003.1-2024 [sigaltstack\(\)](#) for the behaviour of the method.

If `ss->ss_flags` is -1, the new sigaltstack will be ignored.

#### Parameters

in	<i>thread</i>	Thread cap of the thread whose sigaltstack is examined and/or modified.
in	<i>ss</i>	The new sigaltstack.
out	<i>oss</i>	The old sigaltstack.


References [sigaltstack\(\)](#), and [sigprocmask\(\)](#).

Referenced by [sigaction\(\)](#), and [sigaltstack\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 15.287.3.7 sigpending()

```
int L4Re::Itas::sigpending (
    L4::Ipc::Cap< L4::Thread > thread,
    sigset_t * set)
```

Query pending signals.

See IEEE Std 1003.1-2024 [sigpending\(\)](#) for details.

#### Parameters

in	<i>thread</i>	Thread cap of the thread whose pending signal are examined.
out	<i>set</i>	Pending signals of thread.

References [setitimer\(\)](#).

Referenced by [sigprocmask\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 15.287.3.8 sigprocmask()

```
int L4Re::Itas::sigprocmask (
    L4::Ipc::Cap< L4::Thread > thread,
    int how,
    sigset_t const * set,
    sigset_t * oldset)
```

Examine or set process signal mask.

See IEEE Std 1003.1-2024 [sigprocmask\(\)](#) for the behaviour or the method.

If `how` is -1, the signal mask is left unchanged.


#### Parameters

in	<i>thread</i>	Thread cap of the thread whose signal mask is examined and/or modified.
in	<i>how</i>	Operation (SIG_BLOCK, SIG_UNBLOCK, SIG_SETMASK or -1).
in	<i>set</i>	The new signal mask.
out	<i>oldset</i>	The old signal mask.

References [sigpending\(\)](#).

Referenced by [sigaltstack\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



#### 15.287.3.9 unregister\_thread()

```
int L4Re::Itas::unregister_thread (
    L4::Ipc::Cap< L4::Thread > thread)
```

Unregister a thread.

The gates for the thread's pager and exception handler will be destroyed. Thus, the thread must be destroyed after the call.

#### Parameters


<i>thread</i>	The destroyed thread.
---------------	-----------------------

References [unregister\\_thread\(\)](#).


Referenced by [unregister\\_thread\(\)](#).



Here is the call graph for this function:



Here is the caller graph for this function:



The documentation for this class was generated from the following file:


- `I4/re/itas`

## 15.288 L4Re::Log Class Reference


[Log](#) interface class.

```
#include <log>
```

Inheritance diagram for L4Re::Log:



Collaboration diagram for L4Re::Log:



## Public Member Functions

- void `printn` (char const \*string, int len) const noexcept  
Print string with length len, NULL characters don't matter.
- void `print` (char const \*string) const noexcept  
Print NULL-terminated string.

## Public Member Functions inherited from [L4::Vcon](#)

- [l4\\_msgtag\\_t send](#) (char const \*buf, unsigned size, [l4\\_utcb\\_t](#) \*utcb=[l4\\_utcb\(\)](#)) const noexcept  
*Send data to `this` virtual console.*
- long [write](#) (char const \*buf, unsigned size, [l4\\_utcb\\_t](#) \*utcb=[l4\\_utcb\(\)](#)) const noexcept  
*Write data to `this` virtual console.*
- int [read](#) (char \*buf, unsigned size, [l4\\_utcb\\_t](#) \*utcb=[l4\\_utcb\(\)](#)) const noexcept  
*Read data from `this` virtual console.*
- int [read\\_with\\_flags](#) (char \*buf, unsigned size, [l4\\_utcb\\_t](#) \*utcb=[l4\\_utcb\(\)](#)) const noexcept  
*Read data from `this` virtual console which also returns flags.*
- [l4\\_msgtag\\_t set\\_attr](#) ([l4\\_vcon\\_attr\\_t](#) const \*attr, [l4\\_utcb\\_t](#) \*utcb=[l4\\_utcb\(\)](#)) const noexcept  
*Set the attributes of `this` virtual console.*
- [l4\\_msgtag\\_t get\\_attr](#) ([l4\\_vcon\\_attr\\_t](#) \*attr, [l4\\_utcb\\_t](#) \*utcb=[l4\\_utcb\(\)](#)) const noexcept  
*Get attributes of `this` virtual console.*

## Public Member Functions inherited from [L4::Icu](#)

- [l4\\_msgtag\\_t bind](#) (unsigned irqnum, [L4::Cap< Triggerable >](#) irq, [l4\\_utcb\\_t](#) \*utcb=[l4\\_utcb\(\)](#)) noexcept  
*Bind an interrupt line of an interrupt controller to an interrupt object.*
- [l4\\_msgtag\\_t unbind](#) (unsigned irqnum, [L4::Cap< Triggerable >](#) irq, [l4\\_utcb\\_t](#) \*utcb=[l4\\_utcb\(\)](#)) noexcept  
*Remove binding of an interrupt line from the interrupt controller object.*
- [l4\\_msgtag\\_t info](#) ([l4\\_icu\\_info\\_t](#) \*info, [l4\\_utcb\\_t](#) \*utcb=[l4\\_utcb\(\)](#)) noexcept  
*Get information about the ICU features.*
- [l4\\_msgtag\\_t msi\\_info](#) ([l4\\_umword\\_t](#) irqnum, [l4\\_uint64\\_t](#) source, [l4\\_icu\\_msi\\_info\\_t](#) \*msi\_info)  
*Get MSI info about IRQ.*
- [l4\\_msgtag\\_t mask](#) (unsigned irqnum, [l4\\_umword\\_t](#) \*label=0, [l4\\_timeout\\_t](#) to=[L4\\_IPC\\_NEVER](#), [l4\\_utcb\\_t](#) \*utcb=[l4\\_utcb\(\)](#)) noexcept  
*Mask an IRQ line.*
- [l4\\_msgtag\\_t set\\_mode](#) (unsigned irqnum, [l4\\_umword\\_t](#) mode, [l4\\_utcb\\_t](#) \*utcb=[l4\\_utcb\(\)](#)) noexcept  
*Set interrupt mode.*

## Public Member Functions inherited from [L4::Irq\\_eoi](#)

- [l4\\_msgtag\\_t unmask](#) (unsigned irqnum, [l4\\_umword\\_t](#) \*label=0, [l4\\_timeout\\_t](#) to=[L4\\_IPC\\_NEVER](#), [l4\\_utcb\\_t](#) \*utcb=[l4\\_utcb\(\)](#)) noexcept  
*Unmask the given interrupt line.*

## Additional Inherited Members

## Protected Types inherited from [L4::Kobject\\_t< Log, L4::Vcon, L4::PROTO\\_EMPTY >](#)

- typedef Log **Class**  
*The target interface type (inheriting from [Kobject\\_t](#)).*
- typedef Typeid::Iface< PROTO, Log > **\_\_Iface**  
*The interface description for the derived class.*
- typedef Typeid::Merge\_list< Typeid::Iface\_list< **\_\_Iface** >, typename L4::Vcon::\_\_Iface\_list > **\_\_Iface\_list**  
*The list of all RPC interfaces provided directly or through inheritance.*

## Protected Types inherited from [L4::Kobject\\_t< Vcon, Icu, L4\\_PROTO\\_LOG >](#)

- typedef [Vcon](#) **Class**  
*The target interface type (inheriting from [Kobject\\_t](#)).*
- typedef Typeid::Iface< PROTO, [Vcon](#) > **\_\_Iface**  
*The interface description for the derived class.*
- typedef Typeid::Merge\_list< Typeid::Iface\_list< [\\_\\_Iface](#) >, typename Icu::\_\_Iface\_list > **\_\_Iface\_list**  
*The list of all RPC interfaces provided directly or through inheritance.*

## Protected Types inherited from [L4::Kobject\\_t< Icu, Irq\\_eoi, L4\\_PROTO\\_IRQ, Type\\_info::Demand\\_t< 1 > >](#)

- typedef [Icu](#) **Class**  
*The target interface type (inheriting from [Kobject\\_t](#)).*
- typedef Typeid::Iface< PROTO, [Icu](#) > **\_\_Iface**  
*The interface description for the derived class.*
- typedef Typeid::Merge\_list< Typeid::Iface\_list< [\\_\\_Iface](#) >, typename Irq\_eoi::\_\_Iface\_list > **\_\_Iface\_list**  
*The list of all RPC interfaces provided directly or through inheritance.*

## Protected Member Functions inherited from [L4::Kobject\\_t< Log, L4::Vcon, L4::PROTO\\_EMPTY >](#)

- [L4::Cap< Class > c](#) () const noexcept  
*Get the capability to ourselves.*

## Protected Member Functions inherited from [L4::Kobject\\_t< Vcon, Icu, L4\\_PROTO\\_LOG >](#)

- [L4::Cap< Class > c](#) () const noexcept  
*Get the capability to ourselves.*

## Protected Member Functions inherited from [L4::Kobject\\_t< Icu, Irq\\_eoi, L4\\_PROTO\\_IRQ, Type\\_info::Demand\\_t< 1 > >](#)

- [L4::Cap< Class > c](#) () const noexcept  
*Get the capability to ourselves.*

## Static Protected Member Functions inherited from [L4::Kobject\\_t< Log, L4::Vcon, L4::PROTO\\_EMPTY >](#)

- static void [\\_\\_check\\_protocols](#) () noexcept  
*Helper to check for protocol conflicts.*

## Static Protected Member Functions inherited from [L4::Kobject\\_t< Vcon, Icu, L4\\_PROTO\\_LOG >](#)

- static void [\\_\\_check\\_protocols](#) () noexcept  
*Helper to check for protocol conflicts.*

## Static Protected Member Functions inherited from

[L4::Kobject\\_t< lcu, Irq\\_eoi, L4\\_PROTO\\_IRQ, Type\\_info::Demand\\_t< 1 > >](#)

- static void `__check_protocols__()` noexcept  
*Helper to check for protocol conflicts.*

### 15.288.1 Detailed Description

[Log](#) interface class.

Definition at line 33 of file [log](#).

### 15.288.2 Member Function Documentation

#### 15.288.2.1 `print()`

```
void L4Re::Log::print (
    char const * string) const    [noexcept]
```

Print NULL-terminated string.

##### Parameters

<i>string</i>	string to print
---------------	-----------------

#### 15.288.2.2 `println()`

```
void L4Re::Log::println (
    char const * string,
    int len) const    [noexcept]
```

Print string with length *len*, NULL characters don't matter.

##### Parameters

<i>string</i>	string to print
<i>len</i>	length of string

The documentation for this class was generated from the following file:


- [l4/re/log](#)

## 15.289 L4Re::Mem\_alloc Class Reference


Memory allocation interface.

```
#include <mem_alloc>
```

Inheritance diagram for L4Re::Mem\_alloc:



Collaboration diagram for L4Re::Mem\_alloc:



## Data Structures

- struct [Stats](#)  
*Statistics about memory-allocator.*

## Public Types

- enum [Mem\\_alloc\\_flags](#) { [Continuous](#) = 0x01 , [Pinned](#) = 0x02 , [Super\\_pages](#) = 0x04 , [Fixed\\_paddr](#) = 0x08 }



*Flags for the allocator.*

## Public Member Functions

- [l4\\_ret\\_t alloc](#) (long size, [L4::Cap](#)< Dataspace > mem, unsigned long flags=0, unsigned long align=0, [l4\\_addr\\_t](#) paddr=0) const noexcept  
*Allocate anonymous memory.*
- long [info](#) ([Stats](#) &stats)  
*Get allocator information.*

## Public Member Functions inherited from [L4::Factory](#)

- [S create](#) ([Cap](#)< void > target, long obj, [l4\\_utcb\\_t](#) \*utcb=[l4\\_utcb](#)()) noexcept  
*Generic create call to the factory.*
- template<typename OBJ>  
[S create](#) ([Cap](#)< OBJ > target, [l4\\_utcb\\_t](#) \*utcb=[l4\\_utcb](#)()) noexcept  
*Create call for typed capabilities.*
- [l4\\_msgtag\\_t create\\_task](#) ([Cap](#)< [Task](#) > const &target\_cap, [l4\\_fpage\\_t](#) \*utcb\_area, [l4\\_utcb\\_t](#) \*utcb=[l4\\_utcb](#)()) noexcept  
*Create a new task.*
- [l4\\_msgtag\\_t create\\_factory](#) ([Cap](#)< [Factory](#) > const &target\_cap, unsigned long limit, [l4\\_utcb\\_t](#) \*utcb=[l4\\_utcb](#)()) noexcept  
*Create a new factory.*
- [l4\\_msgtag\\_t create\\_gate](#) ([Cap](#)< void > const &target\_cap, [Cap](#)< [Snd\\_destination](#) > const &snd\_dst\_cap, [l4\\_umword\\_t](#) label, [l4\\_utcb\\_t](#) \*utcb=[l4\\_utcb](#)()) noexcept  
*Create a new IPC gate, optionally bound to a send destination (a thread or thread group).*
- [l4\\_msgtag\\_t create\\_thread\\_group](#) ([Cap](#)< [Thread\\_group](#) > const &target\_cap, unsigned policy, [l4\\_utcb\\_t](#) \*utcb=[l4\\_utcb](#)()) noexcept  
*Create a new thread group.*

## Public Member Functions inherited from [L4::Kobject](#)

- [l4\\_msgtag\\_t dec\\_refcnt](#) ([l4\\_mword\\_t](#) diff, [l4\\_utcb\\_t](#) \*utcb=[l4\\_utcb](#)())  
*Decrement the in kernel reference counter for the object.*

## Additional Inherited Members

## Protected Types inherited from

[L4::Kobject\\_t](#)< [Mem\\_alloc](#), [L4::Factory](#), [L4RE\\_PROTO\\_MEM\\_ALLOC](#) >

- typedef [Mem\\_alloc](#) **Class**  
*The target interface type (inheriting from [Kobject\\_t](#)).*
- typedef [Typeid::Iface](#)< [PROTO](#), [Mem\\_alloc](#) > **\_\_Iface**  
*The interface description for the derived class.*
- typedef [Typeid::Merge\\_list](#)< [Typeid::Iface\\_list](#)< **\_\_Iface** >, typename [L4::Factory::\\_\\_Iface\\_list](#) > **\_\_Iface\_list**  
*The list of all RPC interfaces provided directly or through inheritance.*

## Protected Types inherited from [L4::Kobject\\_t< Factory, Kobject, L4\\_PROTO\\_FACTORY >](#)

- typedef [Factory](#) **Class**  
*The target interface type (inheriting from [Kobject\\_t](#)).*
- typedef Typeid::Iface< PROTO, [Factory](#) > **\_\_Iface**  
*The interface description for the derived class.*
- typedef Typeid::Merge\_list< Typeid::Iface\_list< **\_\_Iface** >, typename Kobject::\_\_Iface\_list > **\_\_Iface\_list**  
*The list of all RPC interfaces provided directly or through inheritance.*

## Protected Member Functions inherited from [L4::Kobject\\_t< Mem\\_alloc, L4::Factory, L4RE\\_PROTO\\_MEM\\_ALLOC >](#)

- [L4::Cap< Class > c](#) () const noexcept  
*Get the capability to ourselves.*

## Protected Member Functions inherited from [L4::Kobject\\_t< Factory, Kobject, L4\\_PROTO\\_FACTORY >](#)

- [L4::Cap< Class > c](#) () const noexcept  
*Get the capability to ourselves.*

## Protected Member Functions inherited from [L4::Kobject](#)

- [l4\\_cap\\_idx\\_t cap](#) () const noexcept  
*Return capability selector.*

## Static Protected Member Functions inherited from [L4::Kobject\\_t< Mem\\_alloc, L4::Factory, L4RE\\_PROTO\\_MEM\\_ALLOC >](#)

- static void **\_\_check\_protocols** () noexcept  
*Helper to check for protocol conflicts.*

## Static Protected Member Functions inherited from [L4::Kobject\\_t< Factory, Kobject, L4\\_PROTO\\_FACTORY >](#)

- static void **\_\_check\_protocols** () noexcept  
*Helper to check for protocol conflicts.*

### 15.289.1 Detailed Description

Memory allocation interface.

The memory-allocator API is the basic API to allocate memory from the [L4Re](#) subsystem. The memory is allocated in terms of dataspace (see [L4Re::Dataspace](#)). The provided dataspace have at least the property that data written to such a dataspace is available as long as the dataspace is not freed or the data is not overwritten. In particular, the memory backing a dataspace from an allocator need not be allocated instantly, but may be allocated lazily on demand.

A memory allocator can provide dataspace with additional properties, such as physically contiguous memory, pre-allocated memory, or pinned memory. To request memory with an additional property the [L4Re::Mem\\_alloc::alloc\(\)](#) method provides a flags parameter. If the concrete implementation of a memory allocator does not support or allow allocation of memory with a certain property, the allocation may be refused.

Definition at line 52 of file [mem\\_alloc](#).

## 15.289.2 Member Enumeration Documentation

### 15.289.2.1 Mem\_alloc\_flags

```
enum L4Re::Mem_alloc::Mem_alloc_flags
```

Flags for the allocator.

They describe requested properties of the allocated memory. Support of these properties by the dataspace provider is optional.

#### Enumerator

Continuous	Allocate physically contiguous memory.
Pinned	Deprecated, use <a href="#">L4Re::Dma_space</a> instead.
Super_pages	Allocate super pages.
Fixed_paddr	Allocate at fixed physical address. Only honored on no-MMU systems. Will fail on MMU systems.

Definition at line 62 of file [mem\\_alloc](#).

## 15.289.3 Member Function Documentation

### 15.289.3.1 alloc()

```
L4_ret_t L4Re::Mem_alloc::alloc (
    long size,
    L4::Cap< Dataspace > mem,
    unsigned long flags = 0,
    unsigned long align = 0,
    L4_addr_t paddr = 0) const [noexcept]
```

Allocate anonymous memory.

#### Parameters

	<i>size</i>	Size in bytes to be requested. Allocation granularity is (super)pages, however, the allocator will store the byte-granular given size as the size of the dataspace and consecutively will use this byte-granular size for servicing the dataspace. Allocators may optionally also implement a maximum allocation strategy: if <i>size</i> is a negative value and <i>flags</i> set the <a href="#">Mem_alloc_flags::Continuous</a> bit, the allocator tries to allocate as much memory as possible leaving an amount of at least <i>-size</i> bytes within the associated quota.
out	<i>mem</i>	Capability slot where the capability to the dataspace is received.
	<i>flags</i>	Special dataspace properties, see <a href="#">Mem_alloc_flags</a>
	<i>align</i>	Log2 alignment of dataspace if supported by allocator, will be at least L4_PAGESHIFT, with Super_pages flag set at least L4_SUPERPAGESHIFT
	<i>paddr</i>	The physical address where the dataspace should be allocated if <a href="#">Mem_alloc_flags::Fixed</a> flag is set.


**Return values**

0	Success
-L4_ERANGE	Given size not supported.
-L4_ENOMEM	Not enough memory available.
<0	IPC error

Definition at line 24 of file [mem\\_alloc\\_impl.h](#).

References [L4::Kobject::cap\(\)](#), [Fixed\\_paddr](#), and [l4\\_error\(\)](#).

Here is the call graph for this function:

**15.289.3.2 info()**

```
long L4Re::Mem_alloc::info (  
    Stats & stats)
```

Get allocator information.

**Parameters**

out	stats	Allocator information
-----	-------	-----------------------


**Return values**

0	Success
<0	IPC error


References [info\(\)](#), and [L4\\_INLINE\\_RPC](#).

Referenced by [info\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



The documentation for this class was generated from the following files:


- [l4/re/mem\\_alloc](#)
- [l4/re/impl/mem\\_alloc\\_impl.h](#)

## 15.290 L4Re::Mem\_alloc::Stats Struct Reference

Statistics about memory-allocator.

```
#include <mem_alloc>
```

Collaboration diagram for L4Re::Mem\_alloc::Stats:



## Data Fields

- [l4\\_size\\_t quota](#)  
*Memory quota of this allocator.*
- [l4\\_size\\_t quota\\_used](#)  
*Amount of currently used quota of this allocator.*
- [l4\\_size\\_t mem\\_limit](#)  
*Maximum amount of memory that can be allocated by this allocator.*
- [l4\\_size\\_t mem\\_used](#)  
*Amount of currently allocated memory.*
- [l4\\_size\\_t mem\\_free](#)  
*Amount of memory that is still available for allocation.*

## 15.290.1 Detailed Description

Statistics about memory-allocator.

Definition at line 74 of file [mem\\_alloc](#).

## 15.290.2 Field Documentation

### 15.290.2.1 mem\_free

```
l4\_size\_t L4Re::Mem_alloc::Stats::mem_free
```

Amount of memory that is still available for allocation.

This field can be lower than [mem\\_limit](#) - [mem\\_used](#). In this case the system may be over-committed and there is globally not enough memory left. Also, if the quota is already used up for sub-factories (see [quota\\_used](#)), there may be not enough quota left.

Definition at line 126 of file [mem\\_alloc](#).

### 15.290.2.2 mem\_limit

```
l4\_size\_t L4Re::Mem_alloc::Stats::mem_limit
```

Maximum amount of memory that can be allocated by this allocator.

Will never exceed the [quota](#) but may be smaller if the system has less memory installed.

Definition at line 102 of file [mem\\_alloc](#).

### 15.290.2.3 mem\_used

`l4_size_t L4Re::Mem_alloc::Stats::mem_used`

Amount of currently allocated memory.

This field represents the amount of memory that is in use by this allocator. It recursively includes the memory used by sub-factories, if any.

Will never exceed `mem_limit` or `quota_used`.

#### Note

Dataspaces may allocate memory lazily! As such, the field will increase only after pages have been allocated to a dataspace.

Definition at line 116 of file `mem_alloc`.

### 15.290.2.4 quota

`l4_size_t L4Re::Mem_alloc::Stats::quota`

Memory quota of this allocator.

Strictly limits the amount of memory that can be allocated. This may be larger than there is actual physical memory available. In particular, the root factory has an artificial quota and returns -1 in this field.

Definition at line 83 of file `mem_alloc`.

### 15.290.2.5 quota\_used

`l4_size_t L4Re::Mem_alloc::Stats::quota_used`

Amount of currently used quota of this allocator.

The amount of used quota is not necessarily linked to the current memory usage. See `mem_used` for this information. The quota of a factory is immediately and fully accounted to the parent factory quota.

This value may even exceed `mem_limit` if the system is over-committed.

Definition at line 94 of file `mem_alloc`.

The documentation for this struct was generated from the following file:


- `l4/re/mem_alloc`

## 15.291 L4Re::Mmio\_space Struct Reference

Interface for memory-like address space accessible via IPC.


```
#include <mmio_space>
```

Inheritance diagram for L4Re::Mmio\_space:





Collaboration diagram for L4Re::Mmio\_space:



## Public Types

- enum [Access\\_width](#) { [Wd\\_8bit](#) = 0 , [Wd\\_16bit](#) = 1 , [Wd\\_32bit](#) = 2 , [Wd\\_64bit](#) = 3 }
- Actual size of the value to read or write.*
- typedef [l4\\_uint64\\_t](#) **Addr**
- Device address.*

## Public Member Functions

- [l4\\_ret\\_t](#) **mmio\_read** ([Addr](#) addr, char width, [l4\\_uint64\\_t](#) \*value)
- Read a value from the given address.*
- [l4\\_ret\\_t](#) **mmio\_write** ([Addr](#) addr, char width, [l4\\_uint64\\_t](#) value)
- Write a value to the given address.*

## Public Member Functions inherited from L4::Kobject

- [l4\\_msgtag\\_t](#) **dec\_refcnt** ([l4\\_mword\\_t](#) diff, [l4\\_utcb\\_t](#) \*utcb=[l4\\_utcb\(\)](#))
- Decrement the in kernel reference counter for the object.*

## Additional Inherited Members

### Protected Types inherited from

[L4::Kobject\\_t](#)< [Mmio\\_space](#), [L4::Kobject](#), [L4RE\\_PROTO\\_MMIO\\_SPACE](#) >

- typedef [Mmio\\_space](#) **Class**  
*The target interface type (inheriting from [Kobject\\_t](#)).*
- typedef Typeid::Iface< [PROTO](#), [Mmio\\_space](#) > **\_\_iface**  
*The interface description for the derived class.*
- typedef Typeid::Merge\_list< Typeid::Iface\_list< [\\_\\_iface](#) >, typename [L4::Kobject::\\_\\_iface\\_list](#) > **\_\_iface\_list**  
*The list of all RPC interfaces provided directly or through inheritance.*

### Protected Member Functions inherited from

[L4::Kobject\\_t](#)< [Mmio\\_space](#), [L4::Kobject](#), [L4RE\\_PROTO\\_MMIO\\_SPACE](#) >

- [L4::Cap](#)< [Class](#) > **c** () const noexcept  
*Get the capability to ourselves.*

### Protected Member Functions inherited from [L4::Kobject](#)

- [l4\\_cap\\_idx\\_t](#) **cap** () const noexcept  
*Return capability selector.*

### Static Protected Member Functions inherited from

[L4::Kobject\\_t](#)< [Mmio\\_space](#), [L4::Kobject](#), [L4RE\\_PROTO\\_MMIO\\_SPACE](#) >

- static void **\_\_check\_protocols\_\_** () noexcept  
*Helper to check for protocol conflicts.*

## 15.291.1 Detailed Description

Interface for memory-like address space accessible via IPC.

This interface defines methods for indirect access to MMIO regions.

Memory mapped IO (MMIO) is used by device drivers to control hardware devices. Access to MMIO regions is assigned to user-level device drivers via mappings of memory pages.

However, there are hardware platforms where MMIO regions for different devices share the same memory page. With respect to security and safety, it is often not allowed to map a memory page to multiple device drivers because the driver of one device could then influence operation of another device, which violates security boundaries.

A solution to that problem is to implement a third (trusted) component that gets exclusive access to the shared memory page, and that drivers can access via IPC with the [Mmio\\_space](#) protocol. This proxy-component can then enforce an access policy.

#### Include File

```
#include <l4/re/mmio_space>
```

Definition at line 45 of file [mmio\\_space](#).

## 15.291.2 Member Enumeration Documentation

### 15.291.2.1 Access\_width

```
enum L4Re::Mmio_space::Access_width
```

Actual size of the value to read or write.

#### Enumerator

Wd_8bit	Value is a byte.
Wd_16bit	Value is a 2-byte word.
Wd_32bit	Value is a 4-byte word.
Wd_64bit	Value is a 8-byte word.

Definition at line 49 of file [mmio\\_space](#).

## 15.291.3 Member Function Documentation

### 15.291.3.1 mmio\_read()

```
l4_ret_t L4Re::Mmio_space::mmio_read (  
    Addr addr,  
    char width,  
    l4_uint64_t * value)
```

Read a value from the given address.

#### Parameters

	<i>addr</i>	Device virtual address to read from. The address must be aligned relative to the access width.
	<i>width</i>	Access width of value to be read, see <a href="#">Access_width</a> .
out	<i>value</i>	Return value. If width is smaller than 64 bit,the upper bits are guaranteed to be 0.


#### Return values

<a href="#">L4_EOK</a>	Success.
<a href="#">-L4_EPERM</a>	Insufficient read rights.
<a href="#">-L4_EINVAL</a>	Address does not exist or cannot be accessed with the given width.


References [mmio\\_read\(\)](#).

Referenced by [mmio\\_read\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 15.291.3.2 mmio\_write()

```

l4_ret_t L4Re::Mmio_space::mmio_write (
    Addr addr,
    char width,
    l4_uint64_t value)
  
```

Write a value to the given address.

#### Parameters

<i>addr</i>	Device virtual address to write to. The address must be aligned relative to the access width.
<i>width</i>	Access width of value to write, see <a href="#">Access_width</a> .
<i>value</i>	Value to write. If width is smaller than 64 bit, the upper bits are ignored.


#### Return values

<a href="#">L4_EOK</a>	Success.
<code>-L4_EPERM</code>	Insufficient write rights.
<code>-L4_EINVAL</code>	Address does not exist or cannot be accessed with the given width.


References [mmio\\_write\(\)](#).

Referenced by [mmio\\_write\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



The documentation for this struct was generated from the following file:


- [l4/re/mmio\\_space](#)

## 15.292 L4Re::Namespace Class Reference


Name-space interface.

```
#include <namespace>
```

Inheritance diagram for L4Re::Namespace:



Collaboration diagram for L4Re::Namespace:



## Public Types

- enum `Register_flags` {  
`Ro` = `L4_CAP_FPAGE_RO` , `Rw` = `L4_CAP_FPAGE_RW` , `Rs` = `L4_CAP_FPAGE_RS` , `Rws` = `L4_CAP_FPAGE_RWS` ,  
`Strong` = `L4_CAP_FPAGE_S` , `Trusted` = `0x008` , `Cap_flags` = `Ro | Rw | Strong | Trusted` , `Link` = `0x100` ,  
`Overwrite` = `0x200` }  
*Flags for registering name spaces.*
- enum `Query_result_flags` { `Partly_resolved` = `0x020` }  
*Flags returned by query IPC, only used internally.*
- enum `Query_timeout` { `To_default` = `3600000` , `To_non_blocking` = `0` }  
*Timeout values for query operation.*

## Public Member Functions

- `l4_ret_t query` (char const \*name, `L4::Cap`< void > const &cap, int timeout=`To_default`, `l4_umword_t` \*local\_id=0, bool iterate=true) const noexcept

*Query the name space for a named object.*

- `l4_ret_t query` (char const \*name, unsigned len, `L4::Cap`< void > const &cap, int timeout=`To_default`, `l4_umword_t` \*local\_id=0, bool iterate=true) const noexcept

*Query the name space for a named object.*

- `l4_ret_t register_obj` (char const \*name, `L4::lpc::Cap`< void > obj, unsigned flags=`Rw`) const noexcept

*Register an object with a name.*

- `l4_ret_t unlink` (char const \*name)

*Remove an entry from the name space.*

## Public Member Functions inherited from `L4::Kobject`

- `l4_msgtag_t dec_refcnt` (`l4_mword_t` diff, `l4_utcb_t` \*utcb=`l4_utcb`())

*Decrement the in kernel reference counter for the object.*

## Additional Inherited Members

## Protected Types inherited from

`L4::Kobject_t`< `Namespace`, `L4::Kobject`, `L4RE_PROTO_NAMESPACE`, `L4::Type_info::Demand_t`< 1 >

- typedef `Namespace` **Class**

*The target interface type (inheriting from `Kobject_t`).*

- typedef `Typeid::Iface`< `PROTO`, `Namespace` > **\_\_iface**

*The interface description for the derived class.*

- typedef `Typeid::Merge_list`< `Typeid::Iface_list`< **\_\_iface** >, typename `L4::Kobject::__iface_list` > **\_\_iface\_list**

*The list of all RPC interfaces provided directly or through inheritance.*

## Protected Member Functions inherited from

`L4::Kobject_t`< `Namespace`, `L4::Kobject`, `L4RE_PROTO_NAMESPACE`, `L4::Type_info::Demand_t`< 1 >

- `L4::Cap`< `Class` > **c** () const noexcept

*Get the capability to ourselves.*

## Protected Member Functions inherited from `L4::Kobject`

- `l4_cap_idx_t cap` () const noexcept

*Return capability selector.*

## Static Protected Member Functions inherited from

`L4::Kobject_t`< `Namespace`, `L4::Kobject`, `L4RE_PROTO_NAMESPACE`, `L4::Type_info::Demand_t`< 1 >

- static void **\_\_check\_protocols** () noexcept

*Helper to check for protocol conflicts.*



## 15.292.1 Detailed Description

Name-space interface.

All name space objects must provide this interface. However, it is not mandatory that a name space object allows to register new capabilities.

The name lookup is done iteratively, this means the hierarchical names are resolved component wise by the client itself.

Definition at line 49 of file [namespace](#).

## 15.292.2 Member Enumeration Documentation

### 15.292.2.1 Query\_result\_flags

```
enum L4Re::Namespace::Query_result_flags
```

Flags returned by query IPC, only used internally.

#### Enumerator

Partly_resolved	Name was only partly resolved.
-----------------	--------------------------------

Definition at line 77 of file [namespace](#).

### 15.292.2.2 Query\_timeout

```
enum L4Re::Namespace::Query_timeout
```

Timeout values for query operation.

#### Enumerator

To_default	Default timeout.
To_non_blocking	Expect callee to answer immediately.

Definition at line 83 of file [namespace](#).

### 15.292.2.3 Register\_flags

```
enum L4Re::Namespace::Register_flags
```

Flags for registering name spaces.

#### Enumerator

Ro	Read-only.
Rw	Read-write.
Rs	Read-only + strong.
Rws	Read-write + strong.
Strong	Strong.
Trusted	Obsolete, do not use.
Link	Obsolete, do not use.
Overwrite	If entry already exists, overwrite it.

Definition at line 57 of file [namespace](#).

## 15.292.3 Member Function Documentation

### 15.292.3.1 query() [1/2]

```
L4_ret_t L4Re::Namespace::query (
    char const * name,
    L4::Cap< void > const & cap,
    int timeout = To_default,
    L4_umword_t * local_id = 0,
    bool iterate = true) const [noexcept]
```

Query the name space for a named object.

#### Parameters

in	<i>name</i>	String to query (without any leading slashes).
out	<i>cap</i>	Capability slot where the received capability will be put.
in	<i>timeout</i>	Timeout of query in milliseconds. The client will only wait if a name has already been registered with the server but no object has yet been attached.
out	<i>local_id</i>	If given, <a href="#">L4_RCV_ITEM_LOCAL_ID</a> will be set for the IPC from the name space, so that if the capability that was received is a local item, the capability ID will be returned with this parameter.
in	<i>iterate</i>	If true, the client will try to resolve names by iteratively calling the name spaces until the name is fully resolved.

#### Return values

---


<code>0</code>	Name could be fully resolved.
<code>&gt;0</code>	Name could only be partly resolved. The number of remaining characters is returned.
<code>-L4_ENOENT</code>	Entry could not be found.
<code>-L4_EAGAIN</code>	Entry exists but no object is yet attached. Try again later.
<code>&lt;0</code>	IPC errors, see <a href="#">l4_error_code_t</a> .

Definition at line 114 of file [namespace\\_impl.h](#).


References [query\(\)](#).

Referenced by [query\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 15.292.3.2 `query()` [2/2]

```

l4_ret_t L4Re::Namespace::query (
    char const * name,
    unsigned len,
    L4::Cap< void > const & cap,
    int timeout = To_default,
    l4_umword_t * local_id = 0,
    bool iterate = true) const [noexcept]
  
```

Query the name space for a named object.

The query string does not necessarily need to be null-terminated.

### Parameters

in	<i>len</i>	Length of the string to query without any terminating null characters.
in	<i>name</i>	String to query (without any leading slashes).
out	<i>cap</i>	Capability slot where the received capability will be put.
in	<i>timeout</i>	Timeout of query in milliseconds. The client will only wait if a name has already been registered with the server but no object has yet been attached.
out	<i>local_id</i>	If given, <a href="#">L4_RCV_ITEM_LOCAL_ID</a> will be set for the IPC from the name space, so that if the capability that was received is a local item, the capability ID will be returned with this parameter.
in	<i>iterate</i>	If true, the client will try to resolve names by iteratively calling the name spaces until the name is fully resolved.


### Return values

<i>0</i>	Name could be fully resolved.
<i>&gt;0</i>	Name could only be partly resolved. The number of remaining characters is returned.
<i>-L4_ENOENT</i>	Entry could not be found.
<i>-L4_EAGAIN</i>	Entry exists but no object is yet attached. Try again later.
<i>&lt;0</i>	IPC errors, see <a href="#">l4_error_code_t</a> .

Definition at line 66 of file [namespace\\_impl.h](#).

References [L4\\_EAGAIN](#), [L4\\_EINVAL](#), [l4\\_sleep\(\)](#), and [L4\\_UNLIKELY](#).

Here is the call graph for this function:



### 15.292.3.3 register\_obj()

```

l4_ret_t L4Re::Namespace::register_obj (
    char const * name,
    L4::Ipc::Cap< void > obj,
    unsigned flags = Rw) const [inline], [noexcept]
  
```

Register an object with a name.

**Parameters**

<i>name</i>	Name under which the object should be registered.
<i>obj</i>	Capability to object to register. An invalid capability may be given to only reserve the name for later use.
<i>flags</i>	Flags to assign to the entry, see <a href="#">L4Re::Namespace::Register_flags</a> . Note that the rights that are assigned to a capability are not only determined by the rights given in these flags but also by the rights with which the <code>obj</code> capability was mapped to the name space.

**Return values**

0	Object was successfully registered with <i>name</i> .
-L4_EEXIST	Name already registered.
-L4_EPERM	Insufficient permissions; see precondition.
-L4_ENOMEM	Server has insufficient resources.
-L4_EINVAL	Invalid parameter.
<0	IPC errors, see <a href="#">l4_error_code_t</a> .

**Precondition**


The invoked [Namespace](#) capability must have the permission [L4\\_CAP\\_FPAGE\\_W](#).

Definition at line 167 of file [namespace](#).

References [L4::Kobject\\_t< Namespace, L4::Kobject, L4RE\\_PROTO\\_NAMESPACE, L4::Type\\_info::Demand\\_t< 1 > >::c\(\)](#), [register\\_obj\(\)](#), and [Rw](#).

Referenced by [register\\_obj\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 15.292.3.4 unlink()

```
l4_ret_t L4Re::Namespace::unlink (
    char const * name) [inline]
```

Remove an entry from the name space.

#### Parameters

<i>name</i>	Name of the entry to remove.
-------------	------------------------------

#### Return values

0	Entry successfully removed.
-L4_ENOENT	Given name does not exist.
-L4_EPERM	Insufficient permissions; see precondition.
-L4_EACCESS	Name cannot be removed.
<0	IPC errors, see <a href="#">l4_error_code_t</a> .

#### Precondition


The invoked [Namespace](#) capability must have the permission [L4\\_CAP\\_FPAGE\\_W](#).

Definition at line 193 of file [namespace](#).

References [L4::Kobject\\_t< Namespace, L4::Kobject, L4RE\\_PROTO\\_NAMESPACE, L4::Type\\_info::Demand\\_t< 1 > >::c\(\)](#), and [unlink\(\)](#).

Referenced by [unlink\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



The documentation for this class was generated from the following files:


- [l4/re/namespace](#)
- [l4/re/impl/namespace\\_impl.h](#)

## 15.293 L4Re::Ned::Cmd\_control Class Reference

Direct control interface for Ned.

```
#include <cmd_control>
```

Collaboration diagram for L4Re::Ned::Cmd\_control:



### Public Member Functions

- long [execute](#) (L4::lpc::String<> cmd) noexcept  
*Execute the given Lua code.*
- long [execute](#) (L4::lpc::String<> cmd, L4::lpc::String< char > \*result) noexcept  
*Execute the given Lua code.*

### 15.293.1 Detailed Description

Direct control interface for Ned.

Definition at line 19 of file [cmd\\_control](#).

## 15.293.2 Member Function Documentation

### 15.293.2.1 execute() [1/2]

```
long L4Re::Ned::Cmd_control::execute (
    L4::Ipc::String<> cmd) [inline], [noexcept]
```

Execute the given Lua code.

#### Parameters

in	<i>cmd</i>	String with Lua code to execute.
----	------------	----------------------------------

#### Return values

<i>L4_EOK</i>	Code was successfully executed.
<i>-L4_EINVAL</i>	Code could not be parsed.
<i>-L4_EIO</i>	Error during code execution.


The code is executed using the global Lua state of ned which is retained between successive calls to execute. Thus you may define data in one call to execute and use it in a subsequent call.

This function does not return any results from the execution of the Lua code itself.

Definition at line 42 of file [cmd\\_control](#).

References [L4::Kobject\\_t< Derived, L4::Kobject, L4::PROTO\\_ANY, Type\\_info::Demand\\_t<> >::c\(\)](#).

Here is the call graph for this function:



### 15.293.2.2 execute() [2/2]

```
long L4Re::Ned::Cmd_control::execute (
    L4::Ipc::String<> cmd,
    L4::Ipc::String< char > * result) [inline], [noexcept]
```

Execute the given Lua code.



**Parameters**

in	<i>cmd</i>	String with Lua code to execute.
out	<i>result</i>	The first return value of the Lua code block as string.

**Return values**


<i>L4_EOK</i>	Code was successfully executed.
<i>-L4_EINVAL</i>	Code could not be parsed.
<i>-L4_EIO</i>	Error during code execution.

The code is executed using the global Lua state of ned which is retained between successive calls to execute. Thus you may define data in one call to execute and use it in a subsequent call.

Definition at line 64 of file [cmd\\_control](#).

References [L4::Kobject\\_t< Derived, L4::Kobject, L4::PROTO\\_ANY, Type\\_info::Demand\\_t<> >::c\(\)](#).

Here is the call graph for this function:



The documentation for this class was generated from the following file:


- `pkg/l4re-core/ned/lib/include/cmd_control`

## 15.294 L4Re::Parent Class Reference


[Parent](#) interface.

```
#include <parent>
```

Inheritance diagram for L4Re::Parent:



Collaboration diagram for L4Re::Parent:



## Public Member Functions

- [l4\\_ret\\_t signal](#) (unsigned long sig, unsigned long val)  
*Send a signal to the parent.*

## Public Member Functions inherited from [L4::Kobject](#)

- [l4\\_msgtag\\_t dec\\_refcnt](#) (l4\_mword\_t diff, l4\_utcb\_t \*utcb=l4\_utcb())  
*Decrement the in kernel reference counter for the object.*

## Additional Inherited Members

## Protected Types inherited from

[L4::Kobject\\_t< Parent, L4::Kobject, L4RE\\_PROTO\\_PARENT >](#)

- typedef Parent **Class**

*The target interface type (inheriting from [Kobject\\_t](#)).*

- `typedef Typeid::Iface< PROTO, Parent > __iface`

*The interface description for the derived class.*

- `typedef Typeid::Merge_list< Typeid::Iface_list< __iface >, typename L4::Kobject::__iface_list > __iface_list`

*The list of all RPC interfaces provided directly or through inheritance.*

## Protected Member Functions inherited from [L4::Kobject\\_t< Parent, L4::Kobject, L4RE\\_PROTO\\_PARENT >](#)

- [L4::Cap< Class > c\(\)](#) const noexcept

*Get the capability to ourselves.*

## Protected Member Functions inherited from [L4::Kobject](#)

- [l4\\_cap\\_idx\\_t cap\(\)](#) const noexcept

*Return capability selector.*

## Static Protected Member Functions inherited from [L4::Kobject\\_t< Parent, L4::Kobject, L4RE\\_PROTO\\_PARENT >](#)

- static void [\\_\\_check\\_protocols\\_\\_\(\)](#) noexcept

*Helper to check for protocol conflicts.*

### 15.294.1 Detailed Description

[Parent](#) interface.

See also

[Parent API](#) for more details about the purpose.

Definition at line 42 of file [parent](#).

### 15.294.2 Member Function Documentation

#### 15.294.2.1 [signal\(\)](#)

```
l4_ret_t L4Re::Parent::signal (
    unsigned long sig,
    unsigned long val)
```

Send a signal to the parent.

#### Parameters

---

<i>sig</i>	Signal to send
<i>val</i>	Value of the signal

### Return values

0	Success
<0	IPC error


### Note

The implementations of this interface in Moe and Ned only recognize the signal 0, in which case they will terminate the application from which the interface was invoked and not return. In this case, `val` is treated as the application's return code. For any other value of `sig`, the method just returns successfully.


References [signal\(\)](#).

Referenced by [signal\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



The documentation for this class was generated from the following file:


- [l4/re/parent](#)

## 15.295 L4Re::Random Struct Reference


Low-bandwidth interface for random number generators.

```
#include <random>
```

Inheritance diagram for L4Re::Random:



Collaboration diagram for L4Re::Random:



### Public Member Functions

- long `get_random` (`l4_size_t` size, `L4::lpc::Array< char, unsigned long > *buffer`)  
Get a random number.

### Public Member Functions inherited from L4::lcu

- `l4_msgtag_t bind` (unsigned irqnum, `L4::Cap< Triggerable > irq`, `l4_utcb_t *utcb=l4_utcb()`) noexcept

*Bind an interrupt line of an interrupt controller to an interrupt object.*

- [l4\\_msgtag\\_t unbind](#) (unsigned irqnum, [L4::Cap](#)< [Triggerable](#) > irq, [l4\\_utcb\\_t](#) \*utcb=[l4\\_utcb\(\)](#)) noexcept

*Remove binding of an interrupt line from the interrupt controller object.*

- [l4\\_msgtag\\_t info](#) ([l4\\_icu\\_info\\_t](#) \*info, [l4\\_utcb\\_t](#) \*utcb=[l4\\_utcb\(\)](#)) noexcept

*Get information about the ICU features.*

- [l4\\_msgtag\\_t msi\\_info](#) ([l4\\_umword\\_t](#) irqnum, [l4\\_uint64\\_t](#) source, [l4\\_icu\\_msi\\_info\\_t](#) \*msi\_info)

*Get MSI info about IRQ.*

- [l4\\_msgtag\\_t mask](#) (unsigned irqnum, [l4\\_umword\\_t](#) \*label=0, [l4\\_timeout\\_t](#) to=[L4\\_IPC\\_NEVER](#), [l4\\_utcb\\_t](#) \*utcb=[l4\\_utcb\(\)](#)) noexcept

*Mask an IRQ line.*

- [l4\\_msgtag\\_t set\\_mode](#) (unsigned irqnum, [l4\\_umword\\_t](#) mode, [l4\\_utcb\\_t](#) \*utcb=[l4\\_utcb\(\)](#)) noexcept

*Set interrupt mode.*

## Public Member Functions inherited from [L4::lrq\\_eoi](#)

- [l4\\_msgtag\\_t unmask](#) (unsigned irqnum, [l4\\_umword\\_t](#) \*label=0, [l4\\_timeout\\_t](#) to=[L4\\_IPC\\_NEVER](#), [l4\\_utcb\\_t](#) \*utcb=[l4\\_utcb\(\)](#)) noexcept

*Unmask the given interrupt line.*

## Additional Inherited Members

## Protected Types inherited from [L4::Kobject\\_t](#)< [Random](#), [L4::lcu](#) >

- typedef [Random](#) **Class**

*The target interface type (inheriting from [Kobject\\_t](#)).*

- typedef [Typeid::Iface](#)< [PROTO\\_ANY](#), [Random](#) > **\_\_Iface**

*The interface description for the derived class.*

- typedef [Typeid::Merge\\_list](#)< [Typeid::Iface\\_list](#)< **\_\_Iface** >, typename [L4::lcu::\\_\\_Iface\\_list](#) > **\_\_Iface\_list**

*The list of all RPC interfaces provided directly or through inheritance.*

## Protected Types inherited from

## [L4::Kobject\\_t](#)< [lcu](#), [lrq\\_eoi](#), [L4\\_PROTO\\_IRQ](#), [Type\\_info::Demand\\_t](#)< 1 > >

- typedef [lcu](#) **Class**

*The target interface type (inheriting from [Kobject\\_t](#)).*

- typedef [Typeid::Iface](#)< [PROTO](#), [lcu](#) > **\_\_Iface**

*The interface description for the derived class.*

- typedef [Typeid::Merge\\_list](#)< [Typeid::Iface\\_list](#)< **\_\_Iface** >, typename [lrq\\_eoi::\\_\\_Iface\\_list](#) > **\_\_Iface\_list**

*The list of all RPC interfaces provided directly or through inheritance.*

## Protected Member Functions inherited from [L4::Kobject\\_t](#)< [Random](#), [L4::lcu](#) >

- [L4::Cap](#)< [Class](#) > **c** () const noexcept

*Get the capability to ourselves.*



**Protected Member Functions inherited from****L4::Kobject\_t< Icu, Irq\_eoi, L4\_PROTO\_IRQ, Type\_info::Demand\_t< 1 > >**

- **L4::Cap< Class > c ()** const noexcept

*Get the capability to ourselves.***Static Protected Member Functions inherited from L4::Kobject\_t< Random, L4::Icu >**

- static void **\_\_check\_protocols\_\_ ()** noexcept

*Helper to check for protocol conflicts.***Static Protected Member Functions inherited from****L4::Kobject\_t< Icu, Irq\_eoi, L4\_PROTO\_IRQ, Type\_info::Demand\_t< 1 > >**

- static void **\_\_check\_protocols\_\_ ()** noexcept

*Helper to check for protocol conflicts.***15.295.1 Detailed Description**

Low-bandwidth interface for random number generators.

The interface offers an ICU interface where a client can register an interrupt to get notified when entropy is available. Support for notifications is optional. If a service does not implement notification, it must return 0 for the number of interrupts in the [info\(\)](#) call. The notification interrupt must have index 0.

**Include File**

```
#include <l4/re/random>
```

Definition at line 33 of file [random](#).

**15.295.2 Member Function Documentation****15.295.2.1 get\_random()**

```
long L4Re::Random::get_random (
    l4_size_t size,
    L4::Ipc::Array< char, unsigned long > * buffer)
```

Get a random number.

**Parameters**

	<i>size</i>	Number of bytes of entropy requested.
out	<i>buffer</i>	<a href="#">Buffer</a> containing the random number. Each byte in the buffer contains 8 bits of randomness.

**Return values**

<code>&gt;=0</code>	Actual size of the returned random number in bytes. This may be less than the requested size. The return value may also be 0 if temporarily no entropy is available.
<code>-L4_EIO</code>	Source of randomness permanently unavailable.
<code>&lt;0</code>	IPC error.

This function should never block. It should immediately return as much entropy as is available. If the call returns less than the requested bytes and a notification interrupt was installed, then the service triggers an interrupt as soon as the remaining entropy is available. That means that when an interrupt is triggered, the service must guarantee that the next call to [get\\_random\(\)](#) returns at least the number of missing bytes for the call that initially triggered the notification.

If [get\\_random\(\)](#) is called while a notification is pending, then the behaviour is implementation-defined.

The documentation for this struct was generated from the following file:


- [l4/re/random](#)

## 15.296 L4Re::Rm Class Reference


[Region](#) map.

```
#include <l4/re/rm>
```

Inheritance diagram for L4Re::Rm:



Collaboration diagram for L4Re::Rm:



## Data Structures

- struct [F](#)  
*Rm flags definitions.*
- class [Unique\\_region](#)  
*Unique region.*
- struct [Region](#)

*A region is a range of virtual addresses which is backed by content.*

- struct [Area](#)

*An area is a range of virtual addresses which is reserved, see [L4Re::Rm::reserve\\_area\(\)](#).*

## Public Types

- enum [Detach\\_result](#) { [Detached\\_ds](#) = 0 , [Kept\\_ds](#) = 1 , [Split\\_ds](#) = 2 , [Detach\\_result\\_mask](#) = 3 , [Detach\\_again](#) = 4 }
- Result values for detach operation.*
- enum [Region\\_flag\\_shifts](#) { [Caching\\_shift](#) = Dataspace::F::Caching\_shift }
- Region flag shifts.*
- enum [Detach\\_flags](#) { [Detach\\_exact](#) = 1 , [Detach\\_overlap](#) = 2 , [Detach\\_keep](#) = 4 }
- Flags for detach operation.*

## Public Member Functions

- [l4\\_ret\\_t reserve\\_area](#) ([l4\\_addr\\_t](#) \*start, unsigned long size, Flags flags=[Flags](#)(0), unsigned char align=[L4\\_PAGESHIFT](#)) const noexcept
- Reserve the given area in the region map.*
- template<typename T>  
[l4\\_ret\\_t reserve\\_area](#) (T \*\*start, unsigned long size, Flags flags=[Flags](#)(0), unsigned char align=[L4\\_PAGESHIFT](#)) const noexcept
- Reserve the given area in the region map.*
- [l4\\_ret\\_t free\\_area](#) ([l4\\_addr\\_t](#) addr)
- Free an area from the region map.*
- [l4\\_ret\\_t attach](#) ([l4\\_addr\\_t](#) \*start, unsigned long size, Flags flags, [L4::lpc::Cap](#)< Dataspace > mem, Offset offs=0, unsigned char align=[L4\\_PAGESHIFT](#), [L4::Cap](#)< [L4::Task](#) > const task=[L4::Cap](#)< [L4::Task](#) >::Invalid, char const \*name=nullptr, Offset backing\_offset=0) const noexcept
- Attach a data space to a region.*
- template<typename T>  
[l4\\_ret\\_t attach](#) (T \*\*start, unsigned long size, Flags flags, [L4::lpc::Cap](#)< Dataspace > mem, Offset offs=0, unsigned char align=[L4\\_PAGESHIFT](#), [L4::Cap](#)< [L4::Task](#) > const task=[L4::Cap](#)< [L4::Task](#) >::Invalid, char const \*name=nullptr, Offset backing\_offset=0) const noexcept
- Attach a data space to a region.*
- [l4\\_ret\\_t detach](#) ([l4\\_addr\\_t](#) addr, [L4::Cap](#)< Dataspace > \*mem, [L4::Cap](#)< [L4::Task](#) > const &task=[This\\_task](#)) const noexcept
- Detach and unmap a region from the address space.*
- [l4\\_ret\\_t detach](#) (void \*addr, [L4::Cap](#)< Dataspace > \*mem, [L4::Cap](#)< [L4::Task](#) > const &task=[This\\_task](#)) const noexcept
- Detach and unmap a region from the address space.*
- [l4\\_ret\\_t detach](#) ([l4\\_addr\\_t](#) start, unsigned long size, [L4::Cap](#)< Dataspace > \*mem, [L4::Cap](#)< [L4::Task](#) > const &task) const noexcept
- Detach and unmap all parts of the regions within the specified interval.*
- [l4\\_ret\\_t find](#) ([l4\\_addr\\_t](#) \*addr, unsigned long \*size, Offset \*offset, [L4Re::Rm::Flags](#) \*flags, [L4::Cap](#)< Dataspace > \*m) noexcept
- Find a region given an address and size.*
- [l4\\_ret\\_t get\\_regions](#) ([l4\\_addr\\_t](#) start, [L4::lpc::Ret\\_array](#)< [Region](#) > regions)
- Return the list of regions whose starting addresses are higher or equal to *start* in the address space managed by this region map.*
- long [get\\_areas](#) ([l4\\_addr\\_t](#) start, [L4::lpc::Ret\\_array](#)< [Area](#) > areas)
- Return the list of areas whose starting addresses are higher or equal to *start* in the address space managed by this region map.*
- [l4\\_ret\\_t get\\_info](#) ([l4\\_addr\\_t](#) addr, [L4::lpc::String](#)< char > &name, Offset &backing\_offset)
- Return auxiliary information of a region.*

## Public Member Functions inherited from [L4::Pager](#)

- [l4\\_msgtag\\_t](#) [page\\_fault](#) ([l4\\_umword\\_t](#) pfa, [l4\\_umword\\_t](#) pc, [L4::lpc::Rcv\\_fpage](#) rwin, [L4::lpc::Opt<L4::lpc::Snd\\_fpage & >](#) fp)

*Page-fault protocol message.*

## Public Member Functions inherited from [L4::io\\_pager](#)

- [l4\\_msgtag\\_t](#) [io\\_page\\_fault](#) ([l4\\_fpage\\_t](#) io\_pfa, [l4\\_umword\\_t](#) pc, [L4::lpc::Rcv\\_fpage](#) rwin, [L4::lpc::Opt<L4::lpc::Snd\\_fpage & >](#) fp)

*IO page fault protocol message.*

## Additional Inherited Members

### Protected Types inherited from

[L4::Kobject\\_t< Rm, L4::Pager, L4RE\\_PROTO\\_RM, L4::Type\\_info::Demand\\_t< 1 > >](#)

- typedef [Rm](#) **Class**  
*The target interface type (inheriting from [Kobject\\_t](#)).*
- typedef Typeid::Iface< PROTO, [Rm](#) > **\_\_Iface**  
*The interface description for the derived class.*
- typedef Typeid::Merge\_list< Typeid::Iface\_list< **\_\_Iface** >, typename [L4::Pager::\\_\\_Iface\\_list](#) > **\_\_Iface\_list**  
*The list of all RPC interfaces provided directly or through inheritance.*

### Protected Types inherited from

[L4::Kobject\\_t< Pager, io\\_pager, L4\\_PROTO\\_PAGE\\_FAULT >](#)

- typedef [Pager](#) **Class**  
*The target interface type (inheriting from [Kobject\\_t](#)).*
- typedef Typeid::Iface< PROTO, [Pager](#) > **\_\_Iface**  
*The interface description for the derived class.*
- typedef Typeid::Merge\_list< Typeid::Iface\_list< **\_\_Iface** >, typename [io\\_pager::\\_\\_Iface\\_list](#) > **\_\_Iface\_list**  
*The list of all RPC interfaces provided directly or through inheritance.*

### Protected Member Functions inherited from

[L4::Kobject\\_t< Rm, L4::Pager, L4RE\\_PROTO\\_RM, L4::Type\\_info::Demand\\_t< 1 > >](#)

- [L4::Cap< Class >](#) **c** () const noexcept  
*Get the capability to ourselves.*

### Protected Member Functions inherited from

[L4::Kobject\\_t< Pager, io\\_pager, L4\\_PROTO\\_PAGE\\_FAULT >](#)

- [L4::Cap< Class >](#) **c** () const noexcept  
*Get the capability to ourselves.*

**Static Protected Member Functions inherited from****[L4::Kobject\\_t< Rm, L4::Pager, L4RE\\_PROTO\\_RM, L4::Type\\_info::Demand\\_t< 1 > >](#)**

- static void **`__check_protocols__`** () noexcept  
*Helper to check for protocol conflicts.*

**Static Protected Member Functions inherited from****[L4::Kobject\\_t< Pager, lo\\_pager, L4\\_PROTO\\_PAGE\\_FAULT >](#)**

- static void **`__check_protocols__`** () noexcept  
*Helper to check for protocol conflicts.*

**15.296.1 Detailed Description**

[Region](#) map.

See also

[Region map API](#) .

Definition at line [81](#) of file [rm](#).

**15.296.2 Member Enumeration Documentation****15.296.2.1 Detach\_flags**

enum [L4Re::Rm::Detach\\_flags](#)

Flags for detach operation.

**Enumerator**

<a href="#">Detach_exact</a>	Do an unmap of the exact region given.
<a href="#">Detach_overlap</a>	Do an unmap of all overlapping regions.
<a href="#">Detach_keep</a>	Do not free the detached data space, ignore the <a href="#">F::Detach_free</a> .

Definition at line [215](#) of file [rm](#).

### 15.296.2.2 Detach\_result

enum `L4Re::Rm::Detach_result`

Result values for detach operation.

#### Enumerator

Detached_ds	Detached data sapce.
Kept_ds	Kept data space.
Split_ds	Splitted data space, and done.
Detach_again	Detached data space, more to do.

Definition at line 89 of file `rm`.

### 15.296.2.3 Region\_flag\_shifts

enum `L4Re::Rm::Region_flag_shifts`

`Region` flag shifts.

#### Enumerator

Caching_shift	Start of <code>Rm</code> cache bits.
---------------	--------------------------------------

Definition at line 100 of file `rm`.

## 15.296.3 Member Function Documentation

### 15.296.3.1 attach() [1/2]

```
l4_ret_t L4Re::Rm::attach (
    l4_addr_t * start,
    unsigned long size,
    Rm::Flags flags,
    L4::Ipc::Cap< Dataspace > mem,
    Rm::Offset offs = 0,
    unsigned char align = L4_PAGESHIFT,
    L4::Cap< L4::Task > const task = L4::Cap<L4::Task>::Invalid,
    char const * name = nullptr,
    Rm::Offset backing_offset = 0) const [noexcept]
```

Attach a data space to a region.

#### Parameters

---



<i>in, out</i>	<i>start</i>	Virtual start address where the region manager shall attach the data space. Will be rounded down to the nearest start of a page. If <a href="#">L4Re::Rm::F::Search_addr</a> is given this value is used as the start address to search for a free virtual memory region and the resulting address is returned here. If <a href="#">L4Re::Rm::F::In_area</a> is given the value is used as a selector for the area (see <a href="#">L4Re::Rm::reserve_area</a> ) to attach the data space to.
	<i>size</i>	Size of the data space to attach (in bytes). Will be rounded up to the nearest multiple of the page size.
	<i>flags</i>	The flags control how and with which rights the dataspace is attached to the region. See <a href="#">L4Re::Rm::F::Attach_flags</a> and <a href="#">L4Re::Rm::F::Region_flags</a> . The caller must specify the desired rights of the attached region explicitly. The default set of rights is empty. If the <a href="#">F::Eager_map</a> flag is set this function may also return <a href="#">L4Re::Dataspace::map</a> error codes if the mapping fails.
	<i>mem</i>	Data space.
	<i>offs</i>	Offset into the data space to use.
	<i>align</i>	Alignment of the virtual region, log2-size, default: a page ( <a href="#">L4_PAGESHIFT</a> ). This is only meaningful if the <a href="#">L4Re::Rm::F::Search_addr</a> flag is used.
	<i>task</i>	Optional destination task of mapping if <a href="#">F::Eager_map</a> flag was passed. If invalid, the mapping is established in the current task. This parameter is only useful if the region manager is for a foreign task.
	<i>name</i>	Optional name of the region.
	<i>backing_offset</i>	Optional value describing an offset into the backing store of this region.

### Return values

0	Success
-L4_ENOENT	No area could be found (see <a href="#">L4Re::Rm::F::In_area</a> )
-L4_EPERM	Operation not allowed.
-L4_EINVAL	
-L4_EADDRNOTAVAIL	The given address is not available.
<0	IPC errors

Makes the whole or parts of a data space visible in the virtual memory of the corresponding task. The corresponding region in the virtual address space is backed with the contents of the dataspace.

### Note

When searching for a free place in the virtual address space, the space between *start* and the end of the virtual address space is searched.


There is no region object created, instead the region is defined by a virtual address within this range (see [L4Re::Rm::find](#)).

Definition at line 35 of file [rm\\_impl.h](#).


References [L4::Kobject\\_t< Rm, L4::Pager, L4RE\\_PROTO\\_RM, L4::Type\\_info::Demand\\_t< 1 > >::c\(\)](#), [L4Re::Rm::F::Eager\\_map](#), [L4Re::Rm::F::Kernel](#), [L4Re::Rm::F::No\\_eager\\_map](#), [L4Re::Rm::F::Reserved](#), and [L4Re::Rm::F::Rights\\_mask](#).

Referenced by [attach\(\)](#), and [free\\_area\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 15.296.3.2 attach() [2/2]

```

template<typename T>
l4_ret_t L4Re::Rm::attach (
    T ** start,
    unsigned long size,
    Flags flags,
    L4::Ipc::Cap< Dataspace > mem,
    Offset offs = 0,
    unsigned char align = L4_PAGESHIFT,
    L4::Cap< L4::Task > const task = L4::Cap<L4::Task>::Invalid,
    char const * name = nullptr,
    Offset backing_offset = 0) const [inline], [noexcept]
  
```

Attach a data space to a region.

#### Parameters

---

<i>in, out</i>	<i>start</i>	Virtual start address where the region manager shall attach the data space. Will be rounded down to the nearest start of a page. If <a href="#">L4Re::Rm::F::Search_addr</a> is given this value is used as the start address to search for a free virtual memory region and the resulting address is returned here. If <a href="#">L4Re::Rm::F::In_area</a> is given the value is used as a selector for the area (see <a href="#">L4Re::Rm::reserve_area</a> ) to attach the data space to.
	<i>size</i>	Size of the data space to attach (in bytes). Will be rounded up to the nearest multiple of the page size.
	<i>flags</i>	The flags control how and with which rights the dataspace is attached to the region. See <a href="#">L4Re::Rm::F::Attach_flags</a> and <a href="#">L4Re::Rm::F::Region_flags</a> . The caller must specify the desired rights of the attached region explicitly. The default set of rights is empty. If the <a href="#">F::Eager_map</a> flag is set this function may also return <a href="#">L4Re::Dataspace::map</a> error codes if the mapping fails.
	<i>mem</i>	Data space.
	<i>offs</i>	Offset into the data space to use.
	<i>align</i>	Alignment of the virtual region, log2-size, default: a page ( <a href="#">L4_PAGESHIFT</a> ). This is only meaningful if the <a href="#">L4Re::Rm::F::Search_addr</a> flag is used.
	<i>task</i>	Optional destination task of mapping if <a href="#">F::Eager_map</a> flag was passed. If invalid, the mapping is established in the current task. This parameter is only useful if the region manager is for a foreign task.
	<i>name</i>	Optional name of the region.
	<i>backing_offset</i>	Optional value describing an offset into the backing store of this region.

### Return values

0	Success
-L4_ENOENT	No area could be found (see <a href="#">L4Re::Rm::F::In_area</a> )
-L4_EPERM	Operation not allowed.
-L4_EINVAL	
-L4_EADDRNOTAVAIL	The given address is not available.
<0	IPC errors

Makes the whole or parts of a data space visible in the virtual memory of the corresponding task. The corresponding region in the virtual address space is backed with the contents of the dataspace.

### Note


When searching for a free place in the virtual address space, the space between *start* and the end of the virtual address space is searched.

There is no region object created, instead the region is defined by a virtual address within this range (see [L4Re::Rm::find](#)).

Definition at line 408 of file [rm](#).

References [attach\(\)](#), and [L4\\_PAGESHIFT](#).

Here is the call graph for this function:



### 15.296.3.3 detach() [1/3]

```

l4_ret_t L4Re::Rm::detach (
    l4_addr_t addr,
    L4::Cap< Dataspace > * mem,
    L4::Cap< L4::Task > const & task = This_task) const [inline], [noexcept]
  
```

Detach and unmap a region from the address space.

#### Parameters

	<i>addr</i>	Virtual address of region, any address within the region is valid.
out	<i>mem</i>	<a href="#">Dataspace</a> that is affected. Give 0 if not interested.
	<i>task</i>	This argument specifies the task where the pages are unmapped. Provide <a href="#">L4::Cap&lt;L4::Task&gt;::Invalid</a> for none. The default is the current task.

#### Return values

<a href="#">L4Re::Rm::Detach_result</a>	On success.
<code>-L4_ENOENT</code>	No region found.
<code>&lt;0</code>	IPC errors

Frees a region in the virtual address space given by *addr* (address type). The corresponding part of the address space is now available again.

Definition at line 762 of file [rm](#).


References [detach\(\)](#), and [Detach\\_overlap](#).

Referenced by [detach\(\)](#), [detach\(\)](#), [detach\(\)](#), [free\\_area\(\)](#), and [get\\_info\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 15.296.3.4 detach() [2/3]

```

l4_ret_t L4Re::Rm::detach (
    l4_addr_t start,
    unsigned long size,
    L4::Cap< Dataspace > * mem,
    L4::Cap< L4::Task > const & task) const [inline], [noexcept]

```

Detach and unmap all parts of the regions within the specified interval.

#### Parameters

	<i>start</i>	Start of area to detach, must be within region.
	<i>size</i>	Size of of area to detach (in bytes).
out	<i>mem</i>	<a href="#">Dataspace</a> that is affected. Give 0 if not interested.
	<i>task</i>	This argument specifies the task where the pages are unmapped. Provide <a href="#">L4::Cap&lt;L4::Task&gt;::Invalid</a> for none. The default is the current task.

#### Return values


<a href="#">L4Re::Rm::Detach_result</a>	On success.
<code>-L4_ENOENT</code>	No region found.
<code>&lt;0</code>	IPC errors

Frees all regions within the interval given by start and size. If a region overlaps the start or the end of the interval this region is only detached partly. If the interval is within one region the original region is split up into two separate regions.

Definition at line 775 of file [rm](#).

References [detach\(\)](#), and [Detach\\_exact](#).

Here is the call graph for this function:



### 15.296.3.5 detach() [3/3]

```

l4_ret_t L4Re::Rm::detach (
    void * addr,
    L4::Cap< Dataspace > * mem,
    L4::Cap< L4::Task > const & task = This_task) const [inline], [noexcept]
  
```

Detach and unmap a region from the address space.

#### Parameters

	<i>addr</i>	Virtual address of region, any address within the region is valid.
out	<i>mem</i>	<a href="#">Dataspace</a> that is affected. Give 0 if not interested.
	<i>task</i>	This argument specifies the task where the pages are unmapped. Provide <a href="#">L4::Cap&lt;L4::Task&gt;::Invalid</a> for none. The default is the current task.

#### Return values


<a href="#">L4Re::Rm::Detach_result</a>	On success.
<code>-L4_ENOENT</code>	No region found.
<code>&lt;0</code>	IPC errors

Frees a region in the virtual address space given by *addr* (address type). The corresponding part of the address space is now available again.

Definition at line 767 of file [rm](#).

References [detach\(\)](#), and [Detach\\_overlap](#).

Here is the call graph for this function:



### 15.296.3.6 find()

```

l4_ret_t L4Re::Rm::find (
    l4_addr_t * addr,
    unsigned long * size,
    Offset * offset,
    L4Re::Rm::Flags * flags,
    L4::Cap< Dataspace > * m) [inline], [noexcept]
  
```

Find a region given an address and size.


#### Parameters


in, out	<i>addr</i>	Address to look for. Returns the start address of the found region.
in, out	<i>size</i>	Size of the area to look for (in bytes). Returns the size of the found region (in bytes).
out	<i>offset</i>	Offset at the beginning of the region within the associated dataspace.
out	<i>flags</i>	Region flags, see <a href="#">F::Region_flags</a> (and <a href="#">F::In_area</a> ).
out	<i>m</i>	Associated dataspace or paging service.

#### Return values

0	Success
-L4_EPERM	Operation not allowed.
-L4_ENOENT	No region found.
<0	IPC errors

This function returns the properties of the region that contains the area described by the *addr* and *size* parameter. If no such region is found but a reserved area, the area is returned and [F::In\\_area](#) is set in *flags*. Note, in the case of an area the *offset* and *m* return values are invalid.




**Note**

The value of the size input parameter should be 1 to assure that a region can be determined unambiguously.

Definition at line 671 of file [rm](#).

References [L4::Kobject\\_t< Rm, L4::Pager, L4RE\\_PROTO\\_RM, L4::Type\\_info::Demand\\_t< 1 > >::c\(\)](#).

Here is the call graph for this function:

**15.296.3.7 free\_area()**

```

l4_ret_t L4Re::Rm::free_area (
    l4_addr_t addr)

```

Free an area from the region map.

**Parameters**

<i>addr</i>	An address within the area to free.
-------------	-------------------------------------

**Return values**

0	Success
-L4_ENOENT	No area found.
<0	IPC errors



**Note**

The data spaces that are attached to that area are not detached by this operation.


**See also**

[reserve\\_area\(\)](#) for more information about areas.

References [attach\(\)](#), [detach\(\)](#), [free\\_area\(\)](#), [L4::Cap\\_base::Invalid](#), and [L4\\_PAGESHIFT](#).

Referenced by [free\\_area\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:

**15.296.3.8 get\_areas()**

```

long L4Re::Rm::get_areas (
    l4_addr_t start,
    L4::Ipc::Ret_array< Area > areas)
  
```

Return the list of areas whose starting addresses are higher or equal to `start` in the address space managed by this region map.

**Parameters**

	<i>start</i>	Virtual address from where to start searching.
--	--------------	--

out	<i>areas</i>	List of areas found in this region map.
-----	--------------	---

### Return values

$\geq 0$	Number of returned areas in the <i>areas</i> array.
$< 0$	IPC errors


### Note

The returned list of areas might not be complete and the caller shall use the function repeatedly with a start address one larger than the end address of the last area from the previous call.

References [get\\_areas\(\)](#), and [get\\_info\(\)](#).

Referenced by [get\\_areas\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 15.296.3.9 get\_info()

```

l4_ret_t L4Re::Rm::get_info (
    l4_addr_t addr,
    L4::Ipc::String< char > & name,
    Offset & backing_offset)
  
```

Return auxiliary information of a region.

This is a debugging feature and might not be available.

#### Parameters

	<i>addr</i>	Virtual address of the region.
out	<i>name</i>	Name of the region.
out	<i>backing_offset</i>	Backing offset information.

#### Return values

<i>0</i>	Success
<i>-L4_ENOENT</i>	<a href="#">Region</a> not found.
<i>-L4_ENOSYS</i>	Function not available.
<i>&lt;0</i>	IPC errors

References [detach\(\)](#).

Referenced by [get\\_areas\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



#### 15.296.3.10 get\_regions()

```

l4_ret_t L4Re::Rm::get_regions (
    l4_addr_t start,
    L4::Ipc::Ret_array< Region > regions)
  
```

Return the list of regions whose starting addresses are higher or equal to `start` in the address space managed by this region map.

#### Parameters

	<code>start</code>	Virtual address from where to start searching.
<code>out</code>	<code>regions</code>	List of regions found in this region map.

#### Return values

<code>&gt;=0</code>	Number of returned regions in the <code>regions</code> array.
<code>&lt;0</code>	IPC errors


#### Note

The returned list of regions might not be complete and the caller shall use the function repeatedly with a start address one larger than the end address of the last region from the previous call.

References [get\\_regions\(\)](#).

Referenced by [get\\_regions\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



**15.296.3.11 reserve\_area()** [1/2]

```
l4_ret_t L4Re::Rm::reserve_area (
    l4_addr_t * start,
    unsigned long size,
    Flags flags = Flags(0),
    unsigned char align = L4_PAGESHIFT) const [inline], [noexcept]
```

Reserve the given area in the region map.

**Parameters**

<i>in, out</i>	<i>start</i>	The virtual start address of the area to reserve. Returns the start address of the area.
	<i>size</i>	The size of the area to reserve (in bytes).
	<i>flags</i>	Flags for the reserved area (see <a href="#">L4Re::Rm::F::Region_flags</a> and <a href="#">L4Re::Rm::F::Attach_flags</a> ).
	<i>align</i>	Alignment of area if searched as bits (log2 value).

**Return values**

0	Success
-L4_EADDRNOTAVAIL	The given area cannot be reserved.
<0	IPC errors

This function reserves an area within the virtual address space managed by the region map. There are two kinds of areas available:

- Reserved areas (*flags* = [L4Re::Rm::F::Reserved](#)), where no data spaces can be attached
- Special purpose areas (*flags* = 0), where data spaces can be attached to the area via the [L4Re::Rm::F::In\\_area](#) flag and a start address within the area itself.


**Note**

When searching for a free place in the virtual address space (with *flags* = [L4Re::Rm::F::Search\\_addr](#)), the space between *start* and the end of the virtual address space is searched.

Definition at line 276 of file [rm](#).

References [L4::Kobject\\_t< Rm, L4::Pager, L4RE\\_PROTO\\_RM, L4::Type\\_info::Demand\\_t< 1 > >::c\(\)](#), and [L4\\_PAGESHIFT](#).

Here is the call graph for this function:



**15.296.3.12 reserve\_area()** [2/2]

```
template<typename T>
l4_ret_t L4Re::Rm::reserve_area (
    T ** start,
    unsigned long size,
    Flags flags = Flags(0),
    unsigned char align = L4_PAGESHIFT) const [inline], [noexcept]
```

Reserve the given area in the region map.

**Parameters**

<i>in, out</i>	<i>start</i>	The virtual start address of the area to reserve. Returns the start address of the area.
	<i>size</i>	The size of the area to reserve (in bytes).
	<i>flags</i>	Flags for the reserved area (see <a href="#">F::Region_flags</a> and <a href="#">F::Attach_flags</a> ).
	<i>align</i>	Alignment of area if searched as bits (log2 value).

**Return values**

0	Success
-L4_EADDRNOTAVAIL	The given area cannot be reserved.
<0	IPC errors

For more information, please refer to the analogous function


See also

[L4Re::Rm::reserve\\_area](#).

Definition at line 304 of file [rm](#).

References [L4::Kobject\\_t< Rm, L4::Pager, L4RE\\_PROTO\\_RM, L4::Type\\_info::Demand\\_t< 1 > >::c\(\)](#), [and L4\\_PAGESHIFT](#).

Here is the call graph for this function:



The documentation for this class was generated from the following files:


- [l4/re/rm](#)
- [l4/re/impl/rm\\_impl.h](#)

## 15.297 L4Re::Rm::Area Struct Reference

An area is a range of virtual addresses which is reserved, see [L4Re::Rm::reserve\\_area\(\)](#).

```
#include <rm>
```

Collaboration diagram for L4Re::Rm::Area:



### 15.297.1 Detailed Description

An area is a range of virtual addresses which is reserved, see [L4Re::Rm::reserve\\_area\(\)](#).

See also

[Region map API](#)

Definition at line 698 of file [rm](#).

The documentation for this struct was generated from the following file:


- [l4/re/rm](#)

## 15.298 L4Re::Rm::F Struct Reference

[Rm](#) flags definitions.

```
#include <rm>
```

Collaboration diagram for L4Re::Rm::F:



## Public Types

- enum [Attach\\_flags](#) : l4\_uint32\_t {  
[Search\\_addr](#) = 0x20000 , [In\\_area](#) = 0x40000 , [Eager\\_map](#) = 0x80000 , [No\\_eager\\_map](#) = 0x100000 ,  
[Attach\\_mask](#) = 0x1f0000 }  
*Flags for attach operation.*
- enum [Region\\_flags](#) : l4\_uint16\_t {  
[Rights\\_mask](#) = 0x0f , [R](#) = Dataspace::F::R , [W](#) = Dataspace::F::W , [X](#) = Dataspace::F::X ,  
[RW](#) = Dataspace::F::RW , [RX](#) = Dataspace::F::RX , [RWX](#) = Dataspace::F::RWX , [Kernel](#) = 0x100 ,  
[Detach\\_free](#) = 0x200 , [Pager](#) = 0x400 , [Reserved](#) = 0x800 , [Caching\\_mask](#) = Dataspace::F::Caching\_mask ,  
[Cache\\_normal](#) = Dataspace::F::Normal , [Cache\\_buffered](#) = Dataspace::F::Bufferable , [Cache\\_uncached](#) =  
Dataspace::F::Uncacheable , [Ds\\_map\\_mask](#) = 0xff ,  
[Region\\_flags\\_mask](#) = 0xffff }  
*Region flags (permissions, cacheability, special).*

### 15.298.1 Detailed Description

[Rm](#) flags definitions.

Definition at line [107](#) of file [rm](#).

### 15.298.2 Member Enumeration Documentation

#### 15.298.2.1 [Attach\\_flags](#)

```
enum L4Re::Rm::F::Attach_flags : l4_uint32_t
```

Flags for attach operation.

#### Enumerator

<a href="#">Search_addr</a>	Search for a suitable address range.
<a href="#">In_area</a>	Search only in area, or map into area.
<a href="#">Eager_map</a>	Eagerly map the attached data space in.
<a href="#">No_eager_map</a>	Prevent eager mapping of the attached data space.
<a href="#">Attach_mask</a>	Mask of all attach flags.

Definition at line [110](#) of file [rm](#).



### 15.298.2.2 Region\_flags

```
enum L4Re::Rm::F::Region_flags : 14_uint16_t
```

[Region](#) flags (permissions, cacheability, special).

#### Enumerator

Rights_mask	<a href="#">Region</a> rights.
R	Readable region.
W	Writable region.
X	Executable region.
RW	Readable and writable region.
RX	Readable and executable region.
RWX	Readable, writable and executable region.
Kernel	Kernel-provided memory (KUMEM).
Detach_free	Free the portion of the data space after detach.
Pager	<a href="#">Region</a> has a pager.
Reserved	<a href="#">Region</a> is reserved (blocked).
Caching_mask	Mask of all <a href="#">Rm</a> cache bits.
Cache_normal	Cache bits for normal cacheable memory. This is the default if no other cache-related flag was specified.
Cache_buffered	Cache bits for buffered (write combining) memory.
Cache_uncached	Cache bits for uncached memory.
Ds_map_mask	Mask for all bits for cache options and rights.
Region_flags_mask	Mask of all region flags.

Definition at line 128 of file [rm](#).

The documentation for this struct was generated from the following file:


- [l4/re/rm](#)

## 15.299 L4Re::Rm::Region Struct Reference

A region is a range of virtual addresses which is backed by content.

```
#include <rm>
```

Collaboration diagram for L4Re::Rm::Region:



## 15.299.1 Detailed Description

A region is a range of virtual addresses which is backed by content.

See also

[Region map API](#)

Definition at line 685 of file [rm](#).

The documentation for this struct was generated from the following file:


- [l4/re/rm](#)

## 15.300 L4Re::Rm::Unique\_region< T > Class Template Reference

Unique region.

```
#include <rm>
```

Inheritance diagram for L4Re::Rm::Unique\_region< T >:



Collaboration diagram for L4Re::Rm::Unique\_region< T >:

L4Re::Rm::Unique_region< T >	
+	Unique_region()
+	Unique_region()
+	Unique_region()
+	Unique_region()
+	operator=()
+	~Unique_region()
+	get()
+	release()
+	reset()
+	reset()
+	is_valid()
+	operator*()
+	operator->()

## Public Member Functions

- **Unique\_region** () noexcept  
*Construct an invalid [Unique\\_region](#).*
- [Unique\\_region](#) (T addr) noexcept  
*Construct a [Unique\\_region](#) from an address.*
- [Unique\\_region](#) (T addr, [L4::Cap](#)< [Rm](#) > const &rm) noexcept  
*Construct a valid [Unique\\_region](#) from an address and a region manager.*
- [Unique\\_region](#) (Unique\_region &&o) noexcept  
*Move-Construct a [Unique\\_region](#).*
- Unique\_region & [operator=](#) (Unique\_region &&o) noexcept  
*Move-assign a [Unique\\_region](#).*
- [~Unique\\_region](#) () noexcept  
*Destructor.*
- T [get](#) () const noexcept  
*Return the address.*
- T [release](#) () noexcept  
*Return the address and invalidate the [Unique\\_region](#).*
- void [reset](#) (T addr, [L4::Cap](#)< [Rm](#) > const &rm) noexcept  
*Set new address and region manager.*
- void **reset** () noexcept  
*Make the [Unique\\_region](#) invalid.*

- `bool is_valid ()` const noexcept  
*Check if the `Unique_region` is valid.*
- `T operator* ()` const noexcept  
*Dereference the address.*
- `T operator-> ()` const noexcept  
*Member access for the address.*

### 15.300.1 Detailed Description

```
template<typename T>
class L4Re::Rm::Unique_region< T >
```

Unique region.

Capture a single region with automatic detach on destruction and unique ownership. Stores the start address and the region-mapper capability internally. A unique region is valid precisely if the internal region-mapper capability is valid. The features for unique ownership and automatic detach are only active for valid unique regions.

Definition at line 434 of file `rm`.

### 15.300.2 Constructor & Destructor Documentation

#### 15.300.2.1 Unique\_region() [1/3]

```
template<typename T>
L4Re::Rm::Unique_region< T >::Unique_region (
    T addr) [inline], [explicit], [noexcept]
```

Construct a `Unique_region` from an address.

No region manager is set.

#### Parameters

<code>addr</code>	The new address
-------------------	-----------------

Definition at line 455 of file `rm`.

**15.300.2.2 Unique\_region()** [2/3]

```
template<typename T>
L4Re::Rm::Unique_region< T >::Unique_region (
    T addr,
    L4::Cap< Rm > const & rm) [inline], [noexcept]
```

Construct a valid [Unique\\_region](#) from an address and a region manager.

**Parameters**

<i>addr</i>	The address
<i>rm</i>	The region manager

Definition at line [464](#) of file [rm](#).

**15.300.2.3 Unique\_region()** [3/3]

```
template<typename T>
L4Re::Rm::Unique_region< T >::Unique_region (
    Unique_region< T > && o) [inline], [noexcept]
```

Move-Construct a [Unique\\_region](#).

**Parameters**

<i>o</i>	L-value reference to other region.
----------	------------------------------------

Definition at line [472](#) of file [rm](#).

**15.300.2.4 ~Unique\_region()**

```
template<typename T>
L4Re::Rm::Unique_region< T >::~~Unique_region () [inline], [noexcept]
```

Destructor.

If the region is valid, call [detach](#).

Definition at line [497](#) of file [rm](#).

### 15.300.3 Member Function Documentation

#### 15.300.3.1 `get()`

```
template<typename T>
T L4Re::Rm::Unique_region< T >::get () const [inline], [noexcept]
```

Return the address.


##### Returns

the address

Definition at line 508 of file `rm`.

Referenced by `L4Re::Util::Event_t< Default_event_payload >::init()`, and `L4Re::Util::Event_t< Default_event_payload >::init_poll()`.

Here is the caller graph for this function:



#### 15.300.3.2 `is_valid()`

```
template<typename T>
bool L4Re::Rm::Unique_region< T >::is_valid () const [inline], [noexcept]
```

Check if the `Unique_region` is valid.

##### Returns

true iff the `Unique_region` is valid

Definition at line 548 of file `rm`.

### 15.300.3.3 operator=()

```
template<typename T>
Unique_region & L4Re::Rm::Unique_region< T >::operator= (
    Unique_region< T > && o) [inline], [noexcept]
```

Move-assign a [Unique\\_region](#).

#### Parameters

<i>o</i>	L-value reference to region to assign from
----------	--

Definition at line [480](#) of file [rm](#).

### 15.300.3.4 release()

```
template<typename T>
T L4Re::Rm::Unique_region< T >::release () [inline], [noexcept]
```

Return the address and invalidate the [Unique\\_region](#).

#### Returns

the address

Definition at line [516](#) of file [rm](#).

### 15.300.3.5 reset()

```
template<typename T>
void L4Re::Rm::Unique_region< T >::reset (
    T addr,
    L4::Cap< Rm > const & rm) [inline], [noexcept]
```

Set new address and region manager.

#### Parameters

<i>addr</i>	The new address
<i>rm</i>	The new region manager

Definition at line [528](#) of file [rm](#).

The documentation for this class was generated from the following file:


- [l4/re/rm](#)

## 15.301 L4Re::Smart\_cap\_auto< Unmap\_flags > Class Template Reference

Helper for [Unique\\_cap](#) and [Unique\\_del\\_cap](#).

```
#include <cap_alloc>
```

Collaboration diagram for L4Re::Smart\_cap\_auto< Unmap\_flags >:



### 15.301.1 Detailed Description

```
template<unsigned long Unmap_flags = L4_FP_ALL_SPACES>
class L4Re::Smart_cap_auto< Unmap_flags >
```

Helper for [Unique\\_cap](#) and [Unique\\_del\\_cap](#).

Definition at line [103](#) of file [cap\\_alloc](#).

The documentation for this class was generated from the following file:

- [l4/re/cap\\_alloc](#)


## 15.302 L4Re::Smart\_count\_cap< Unmap\_flags > Class Template Reference

Helper for [Ref\\_cap](#) and [Ref\\_del\\_cap](#).

```
#include <cap_alloc>
```



Collaboration diagram for L4Re::Smart\_count\_cap< Unmap\_flags >:



### Public Member Functions

- void **free** ([L4::Cap\\_base](#) &c) noexcept  
*Free operation for [L4::Smart\\_cap](#) (decrement ref count and delete if 0).*
- [L4::Cap\\_base](#) **copy** ([L4::Cap\\_base](#) const &src)  
*Copy operation for [L4::Smart\\_cap](#) (increment ref count).*

### Static Public Member Functions

- static void **invalidate** ([L4::Cap\\_base](#) &c) noexcept  
*Invalidate operation for [L4::Smart\\_cap](#).*

## 15.302.1 Detailed Description

```
template<unsigned long Unmap_flags = L4_FP_ALL_SPACES>
class L4Re::Smart_count_cap< Unmap_flags >
```

Helper for Ref\_cap and Ref\_del\_cap.

Definition at line 132 of file [cap\\_alloc](#).

The documentation for this class was generated from the following file:


- [l4/re/cap\\_alloc](#)

### 15.303 L4Re::Util::\_Cap\_alloc Class Reference


Adapter to expose the cap allocator implementation as [L4Re::Cap\\_alloc](#) compatible class.

```
#include <cap_alloc_impl.h>
```

Inheritance diagram for L4Re::Util::\_Cap\_alloc:



Collaboration diagram for L4Re::Util::\_Cap\_alloc:



### Public Member Functions

- `L4::Cap< void > alloc ()` noexcept override  
*Allocate a capability.*
- `template<typename T>`  
`L4::Cap< T > alloc ()` noexcept  
*Allocate a capability.*
- `void free (L4::Cap< void > cap, l4_cap_idx_t task=L4_INVALID_CAP, unsigned unmap_flags=L4_FP_ALL_SPACES)` noexcept override  
*Free a capability.*

### Public Member Functions inherited from L4Re::Cap\_alloc

- `template<typename T>`  
`L4::Cap< T > alloc ()` noexcept  
*Allocate a capability.*

## 15.303.1 Detailed Description

Adapter to expose the cap allocator implementation as `L4Re::Cap_alloc` compatible class.

Not intended to be used in application code.

Definition at line 66 of file `cap_alloc_impl.h`.

## 15.303.2 Member Function Documentation

### 15.303.2.1 `alloc()` [1/2]

```
template<typename T>
L4::Cap< T > L4Re::Util::_Cap_alloc::alloc () [inline], [virtual], [noexcept]
```

Allocate a capability.

#### Returns


Capability of type void

Implements [L4Re::Cap\\_alloc](#).

Definition at line 79 of file [cap\\_alloc\\_impl.h](#).

References [alloc\(\)](#), and [L4::cap\\_cast\(\)](#).

Here is the call graph for this function:



### 15.303.2.2 `alloc()` [2/2]

```
L4::Cap< void > L4Re::Util::_Cap_alloc::alloc () [inline], [override], [virtual], [noexcept]
```

Allocate a capability.

#### Returns


Capability of type void

Implements [L4Re::Cap\\_alloc](#).

Definition at line 75 of file [cap\\_alloc\\_impl.h](#).

Referenced by [alloc\(\)](#).

Here is the caller graph for this function:



### 15.303.2.3 free()

```
void L4Re::Util::_Cap_alloc::free (
    L4::Cap< void > cap,
    l4_cap_idx_t task = L4_INVALID_CAP,
    unsigned unmap_flags = L4_FP_ALL_SPACES) [inline], [override], [virtual], [noexcept]
```

Free a capability.

#### Parameters

<i>cap</i>	Capability to free.
<i>task</i>	If set, task to unmap the capability from.
<i>unmap_flags</i>	Flags for unmap, see <a href="#">l4_unmap_flags_t</a> .

Implements [L4Re::Cap\\_alloc](#).

Definition at line 85 of file [cap\\_alloc\\_impl.h](#).

References [L4Re::Util::L4\\_FP\\_ALL\\_SPACES](#), and [L4\\_INVALID\\_CAP](#).

The documentation for this class was generated from the following file:


- [l4/re/util/cap\\_alloc\\_impl.h](#)

## 15.304 L4Re::Util::Bitmap< BITS > Class Template Reference


A static bitmap.

```
#include <bitmap>
```

Inheritance diagram for L4Re::Util::Bitmap< BITS >:



Collaboration diagram for L4Re::Util::Bitmap< BITS >:



## Public Member Functions

- **Bitmap** () noexcept  
*Create a bitmap with `BITS` bits.*
- long [scan\\_zero](#) (long start\_bit=0) const noexcept  
*Scan for the first zero bit.*

## Public Member Functions inherited from [cxx::Bitmap\\_base](#)

- void [bit](#) (long bit, bool on) noexcept

- Set the value of bit *bit* to on.

  - void `clear_bit` (long *bit*) noexcept

Clear bit *bit*.
- void `atomic_clear_bit` (long *bit*) noexcept

Clear bit *bit* atomically.
- `word_type atomic_get_and_clear` (long *bit*) noexcept

Clear bit *bit* atomically and return old state.
- void `set_bit` (long *bit*) noexcept

Set bit *bit*.
- void `atomic_set_bit` (long *bit*) noexcept

Set bit *bit* atomically.
- `word_type atomic_get_and_set` (long *bit*) noexcept

Set bit *bit* atomically and return old state.
- `word_type bit` (long *bit*) const noexcept

Get the truth value of a bit.
- `word_type operator[]` (long *bit*) const noexcept

Get the bit at index *bit*.
- `Bit operator[]` (long *bit*) noexcept

Get the lvalue for the bit at index *bit*.
- long `scan_zero` (long max\_bit, long start\_bit=0) const noexcept

Scan for the first zero bit.

### Additional Inherited Members

### Static Public Member Functions inherited from `cxx::Bitmap_base`

- static long `words` (long bits) noexcept
- Get the number of *words* that are used for the bitmap.
- static long `chars` (long bits) noexcept
- Get the number of *chars* that are used for the bitmap.

### Protected Types inherited from `cxx::Bitmap_base`

- enum { `W_bits` = sizeof(word\_type) \* 8 , `C_bits` = 8 }
  - typedef unsigned long `word_type`
- Data type for each element of the bit buffer.

### Static Protected Member Functions inherited from `cxx::Bitmap_base`

- static unsigned `word_index` (unsigned *bit*)
- Get the word index for the given bit.
- static unsigned `bit_index` (unsigned *bit*)
- Get the bit index within *word\_type* for the given bit.

### Protected Attributes inherited from `cxx::Bitmap_base`

- `word_type * _bits`
- Pointer to the buffer storing the bits.



## 15.304.1 Detailed Description

```
template<int BITS>
class L4Re::Util::Bitmap< BITS >
```

A static bitmap.

### Template Parameters

<i>BITS</i>	The number of bits that shall be in the bitmap.
-------------	---

Definition at line 220 of file [bitmap](#).

## 15.304.2 Member Function Documentation

### 15.304.2.1 scan\_zero()

```
template<int BITS>
long cxx::Bitmap< BITS >::scan_zero (
    long start_bit = 0) const [inline], [noexcept]
```

Scan for the first zero bit.

### Parameters

<i>start_bit</i>	Hint at the number of the first bit to look at. Zero bits below <i>start_bit</i> may or may not be taken into account by the implementation.
------------------	--

### Return values

<i>&gt;=</i>	0 Number of first zero bit found.
<i>-1</i>	All bits at <i>start_bit</i> or higher are set.

Compared to [Bitmap\\_base::scan\\_zero\(\)](#), the upper bound is set to BITS.

Definition at line 365 of file [bitmap](#).

The documentation for this class was generated from the following file:


- I4/cxx/bitmap

## 15.305 L4Re::Util::Bitmap\_base Class Reference

Basic bitmap abstraction.

```
#include <bitmap>
```

Inheritance diagram for L4Re::Util::Bitmap\_base:



Collaboration diagram for L4Re::Util::Bitmap\_base:

L4Re::Util::Bitmap_base
# _bits
+ bit()
+ bit()
+ clear_bit()
+ atomic_clear_bit()
+ atomic_get_and_clear()
+ set_bit()
+ atomic_set_bit()
+ atomic_get_and_set()
+ operator[]()
+ operator[]()
+ scan_zero()
+ words()
+ chars()
# word_index()
# bit_index()

## Data Structures

- class [Bit](#)  
*A writable bit in a bitmap.*
- class [Word](#)  
*Helper abstraction for a word contained in the bitmap.*
- class [Char](#)  
*Helper abstraction for a byte contained in the bitmap.*

## Public Member Functions

- void [bit](#) (long bit, bool on) noexcept  
*Set the value of bit [bit](#) to on.*
- [word\\_type](#) [bit](#) (long bit) const noexcept  
*Get the truth value of a bit.*
- void [clear\\_bit](#) (long [bit](#)) noexcept  
*Clear bit [bit](#).*
- void [atomic\\_clear\\_bit](#) (long [bit](#)) noexcept  
*Clear bit [bit](#) atomically.*

- `word_type atomic_get_and_clear` (long `bit`) noexcept  
*Clear bit `bit` atomically and return old state.*
- void `set_bit` (long `bit`) noexcept  
*Set bit `bit`.*
- void `atomic_set_bit` (long `bit`) noexcept  
*Set bit `bit` atomically.*
- `word_type atomic_get_and_set` (long `bit`) noexcept  
*Set bit `bit` atomically and return old state.*
- `word_type operator[]` (long `bit`) const noexcept  
*Get the bit at index `bit`.*
- `Bit operator[]` (long `bit`) noexcept  
*Get the lvalue for the bit at index `bit`.*
- long `scan_zero` (long max\_bit, long start\_bit=0) const noexcept  
*Scan for the first zero bit.*

### Static Public Member Functions

- static long `words` (long bits) noexcept  
*Get the number of words that are used for the bitmap.*
- static long `chars` (long bits) noexcept  
*Get the number of chars that are used for the bitmap.*

### Protected Types

- enum { `W_bits` = sizeof(word\_type) \* 8 , `C_bits` = 8 }
- typedef unsigned long `word_type`  
*Data type for each element of the bit buffer.*

### Static Protected Member Functions

- static unsigned `word_index` (unsigned `bit`)  
*Get the word index for the given bit.*
- static unsigned `bit_index` (unsigned `bit`)  
*Get the bit index within `word_type` for the given bit.*

### Protected Attributes

- `word_type * _bits`  
*Pointer to the buffer storing the bits.*

## 15.305.1 Detailed Description

Basic bitmap abstraction.

This abstraction keeps a pointer to a memory area that is used as bitmap.

Definition at line 18 of file `bitmap`.

## 15.305.2 Member Enumeration Documentation

### 15.305.2.1 anonymous enum

anonymous enum [protected]

#### Enumerator

W_bits	number of bits in <a href="#">word_type</a>
C_bits	number of bits in char

Definition at line 26 of file [bitmap](#).

## 15.305.3 Member Function Documentation

### 15.305.3.1 atomic\_clear\_bit()

```
void cxx::Bitmap\_base::atomic\_clear\_bit (  
    long bit) [inline], [noexcept]
```

Clear bit [bit](#) atomically.

Use this function for multi-threaded access to the bitmap.

#### Parameters

<i>bit</i>	The number of the bit to clear.
------------	---------------------------------

Definition at line 269 of file [bitmap](#).

### 15.305.3.2 atomic\_get\_and\_clear()

```
Bitmap\_base::word\_type cxx::Bitmap\_base::atomic\_get\_and\_clear (  
    long bit) [inline], [noexcept]
```

Clear bit [bit](#) atomically and return old state.

Use this function for multi-threaded access to the bitmap.

#### Parameters

<i>bit</i>	The number of the bit to clear.
------------	---------------------------------

Definition at line 279 of file [bitmap](#).

### 15.305.3.3 atomic\_get\_and\_set()

```
Bitmap_base::word_type cxx::Bitmap_base::atomic_get_and_set (
    long bit) [inline], [noexcept]
```

Set bit `bit` atomically and return old state.

Use this function for multi-threaded access to the bitmap.

#### Parameters

<i>bit</i>	The number of the bit to set.
------------	-------------------------------

Definition at line 308 of file `bitmap`.

### 15.305.3.4 atomic\_set\_bit()

```
void cxx::Bitmap_base::atomic_set_bit (
    long bit) [inline], [noexcept]
```

Set bit `bit` atomically.

Use this function for multi-threaded access to the bitmap.

#### Parameters

<i>bit</i>	The number of the bit to set.
------------	-------------------------------

Definition at line 298 of file `bitmap`.

### 15.305.3.5 bit() [1/2]

```
Bitmap_base::word_type cxx::Bitmap_base::bit (
    long bit) const [inline], [noexcept]
```

Get the truth value of a bit.

#### Parameters

<i>bit</i>	The number of the bit to read.
------------	--------------------------------

#### Return values

0	Bit is not set.
!= 0	Bit is set.

Definition at line 318 of file `bitmap`.

### 15.305.3.6 bit() [2/2]

```
void cxx::Bitmap_base::bit (
    long bit,
    bool on) [inline], [noexcept]
```

Set the value of bit `bit` to on.

#### Parameters

<i>bit</i>	The number of the bit.
<i>on</i>	The boolean value that shall be assigned to the bit.

Definition at line 251 of file `bitmap`.

### 15.305.3.7 bit\_index()

```
unsigned cxx::Bitmap_base::bit_index (
    unsigned bit) [inline], [static], [protected]
```

Get the bit index within `word_type` for the given bit.

#### Parameters

<i>bit</i>	The bit index in the bitmap.
------------	------------------------------

#### Returns

the bit index within `word_type` (bit % W\_bits).

Definition at line 53 of file `bitmap`.

### 15.305.3.8 clear\_bit()

```
void cxx::Bitmap_base::clear_bit (
    long bit) [inline], [noexcept]
```

Clear bit `bit`.

#### Parameters

<i>bit</i>	The number of the bit to clear.
------------	---------------------------------

Definition at line 260 of file `bitmap`.

### 15.305.3.9 operator[]() [1/2]

```
word_type cxx::Bitmap_base::operator[] (
    long bit) const [inline], [noexcept]
```

Get the bit at index `bit`.

#### Parameters

<i>bit</i>	The number of the bit to read.
------------	--------------------------------

#### Return values

0	Bit is not set.
!= 0	Bit is set.

Definition at line 181 of file `bitmap`.

### 15.305.3.10 operator[]() [2/2]

```
Bit cxx::Bitmap_base::operator[] (
    long bit) [inline], [noexcept]
```

Get the lvalue for the bit at index `bit`.

#### Parameters

<i>bit</i>	The number.
------------	-------------

#### Returns

lvalue for `bit`

Definition at line 191 of file `bitmap`.

### 15.305.3.11 scan\_zero()

```
long cxx::Bitmap_base::scan_zero (
    long max_bit,
    long start_bit = 0) const [inline], [noexcept]
```

Scan for the first zero bit.

#### Parameters

<i>max_bit</i>	Upper bound (exclusive) for the scanning operation.
----------------	---



<i>start_bit</i>	Hint at the number of the first bit to look at. Zero bits below <i>start_bit</i> may or may not be taken into account by the implementation.
------------------	--

### Return values

<i>&gt;=</i>	0 Number of first zero bit found.
<i>-1</i>	All bits between <i>start_bit</i> and <i>max_bit</i> are set.

Definition at line 339 of file [bitmap](#).

### 15.305.3.12 set\_bit()

```
void cxx::Bitmap_base::set_bit (
    long bit) [inline], [noexcept]
```

Set bit *bit*.

### Parameters

<i>bit</i>	The number of the bit to set.
------------	-------------------------------

Definition at line 289 of file [bitmap](#).

### 15.305.3.13 word\_index()

```
unsigned cxx::Bitmap_base::word_index (
    unsigned bit) [inline], [static], [protected]
```

Get the word index for the given bit.

### Parameters

<i>bit</i>	The index of the bit in question.
------------	-----------------------------------

### Returns

the index in [Bitmap\\_base::\\_bits](#) for the given bit (bit / W\_bits).

Definition at line 44 of file [bitmap](#).

The documentation for this class was generated from the following file:


- I4/cxx/bitmap

## 15.306 L4Re::Util::Bitmap\_base::Bit Class Reference

A writable bit in a bitmap.

```
#include <bitmap>
```

Collaboration diagram for L4Re::Util::Bitmap\_base::Bit:



### 15.306.1 Detailed Description

A writable bit in a bitmap.

Definition at line 58 of file [bitmap](#).

The documentation for this class was generated from the following file:


- I4/cxx/bitmap

## 15.307 L4Re::Util::Bitmap\_base::Char< BITS > Class Template Reference

Helper abstraction for a byte contained in the bitmap.

```
#include <bitmap>
```

Collaboration diagram for L4Re::Util::Bitmap\_base::Char< BITS >:



### 15.307.1 Detailed Description

```
template<long BITS>
class L4Re::Util::Bitmap_base::Char< BITS >
```

Helper abstraction for a byte contained in the bitmap.

Definition at line 95 of file [bitmap](#).

The documentation for this class was generated from the following file:


- I4/cxx/bitmap

## 15.308 L4Re::Util::Bitmap\_base::Word< BITS > Class Template Reference


Helper abstraction for a word contained in the bitmap.

```
#include <bitmap>
```

Inheritance diagram for L4Re::Util::Bitmap\_base::Word< BITS >:



Collaboration diagram for L4Re::Util::Bitmap\_base::Word< BITS >:



### 15.308.1 Detailed Description

```
template<long BITS>
class L4Re::Util::Bitmap_base::Word< BITS >
```

Helper abstraction for a word contained in the bitmap.

Definition at line 79 of file [bitmap](#).

The documentation for this class was generated from the following file:


- I4/cxx/bitmap

## 15.309 L4Re::Util::Br\_manager Class Reference


Buffer-register (BR) manager for [L4::Server](#).

```
#include <br_manager>
```

Inheritance diagram for L4Re::Util::Br\_manager:



Collaboration diagram for L4Re::Util::Br\_manager:



## Public Member Functions

- **Br\_manager ()**  
*Make a buffer-register (BR) manager.*
- int **alloc\_buffer\_demand** (**Demand** const &d) override  
*Tells the server to allocate buffers for the given demand.*
- **L4::Cap**< void > **get\_rcv\_cap** (int i) const override  
*Get capability slot allocated to the given receive buffer.*
- int **realloc\_rcv\_cap** (int i) override  
*Allocate a new capability for the given receive buffer.*
- void **set\_rcv\_cap\_flags** (unsigned long flags)

*Set the receive flags for the buffers.*

- int **add\_timeout** ([L4::lpc\\_svr::Timeout](#) \*, [l4\\_kernel\\_clock\\_t](#)) override

*No timeouts handled by us.*

- int **remove\_timeout** ([L4::lpc\\_svr::Timeout](#) \*) override

*No timeouts handled by us.*

- void **setup\_wait** ([l4\\_utcb\\_t](#) \*utcb, [L4::lpc\\_svr::Reply\\_mode](#))

*[setup\\_wait\(\)](#) used the server loop ([L4::Server](#))*

## Public Member Functions inherited from [L4::lpc\\_svr::Server\\_iface](#)

- **Server\_iface** ()

*Make a server interface.*

- template<typename T>

[L4::Cap](#)< T > **rcv\_cap** (int index) const

*Get given receive buffer as typed capability.*

- [L4::Cap](#)< void > **rcv\_cap** (int index) const

*Get receive cap with the given index as generic (void) type.*

## Protected Member Functions

- unsigned **first\_free\_br** () const

*Used for assigning BRs for a timeout.*

## Additional Inherited Members

## Public Types inherited from [L4::lpc\\_svr::Server\\_iface](#)

- typedef [L4::Type\\_info::Demand](#) **Demand**

*Data type expressing server-side demand for receive buffers.*

### 15.309.1 Detailed Description

Buffer-register (BR) manager for [L4::Server](#).

Implementation of the [L4::lpc\\_svr::Server\\_iface](#) API for managing the server-side receive buffers needed for a set of server objects running within a server.

Definition at line 25 of file [br\\_manager](#).

## 15.309.2 Member Function Documentation

### 15.309.2.1 `alloc_buffer_demand()`

```
int L4Re::Util::Br_manager::alloc_buffer_demand (
    Demand const & demand) [inline], [override], [virtual]
```

Tells the server to allocate buffers for the given demand.

#### Parameters

<i>demand</i>	The total server-side demand of receive buffers needed for a given interface, see <a href="#">Demand</a> .
---------------	--


This function is not called by user applications directly. Usually the server implementation or the registry implementation calls this function whenever a new object is registered at the server.

Implements [L4::lpc\\_svr::Server\\_iface](#).

Definition at line 54 of file [br\\_manager](#).

References [L4::Cap\\_base::cap\(\)](#), [L4Re::Util::cap\\_alloc](#), [L4::Type\\_info::Demand::caps](#), [L4\\_EINVAL](#), [L4\\_ENOMEM](#), [L4\\_EOK](#), [L4\\_ERANGE](#), [L4::Type\\_info::Demand::mem](#), and [L4::Type\\_info::Demand::ports](#).

Here is the call graph for this function:



### 15.309.2.2 `get_rcv_cap()`

```
L4::Cap< void > L4Re::Util::Br_manager::get_rcv_cap (
    int index) const [inline], [override], [virtual]
```

Get capability slot allocated to the given receive buffer.

#### Parameters

<i>index</i>	The receive buffer index of the expected capability argument ( $0 \leq \text{index} < \text{caps}$ registered with <a href="#">alloc_buffer_demand()</a> ).
--------------	---

#### Precondition

$0 \leq \text{index} < \text{caps}$  registered with [alloc\\_buffer\\_demand\(\)](#)

#### Returns

Capability slot currently allocated to the given receive buffer.

Implements [L4::lpc\\_svr::Server\\_iface](#).

Definition at line 86 of file [br\\_manager](#).

References [L4::Cap\\_base::Invalid](#), and [L4\\_CAP\\_MASK](#).



### 15.309.2.3 realloc\_rcv\_cap()

```
int L4Re::Util::Br_manager::realloc_rcv_cap (  
    int index) [inline], [override], [virtual]
```

Allocate a new capability for the given receive buffer.

#### Parameters

<i>index</i>	The receive buffer index of the expected capability argument ( $0 \leq \text{index} < \text{caps}$ registered with <a href="#">alloc_buffer_demand()</a> ).
--------------	---

#### Precondition

$0 \leq \text{index} < \text{caps}$  registered with [alloc\\_buffer\\_demand\(\)](#)

#### Returns


0 on success, < 0 on error.

Implements [L4::lpc\\_svr::Server\\_iface](#).

Definition at line 94 of file [br\\_manager](#).

References [L4::Cap\\_base::cap\(\)](#), [L4Re::Util::cap\\_alloc](#), [L4\\_EINVAL](#), [L4\\_ENOMEM](#), and [L4\\_EOK](#).

Here is the call graph for this function:



### 15.309.2.4 set\_rcv\_cap\_flags()

```
void L4Re::Util::Br_manager::set_rcv_cap_flags (  
    unsigned long flags) [inline]
```

Set the receive flags for the buffers.

**Precondition**

Must be called before any handlers are registered.

**Parameters**

<i>flags</i>	New receive capability flags, see <a href="#">l4_msg_item_consts_t</a> .
--------------	--

Definition at line 118 of file [br\\_manager](#).

References [l4\\_assert](#).

The documentation for this class was generated from the following file:


- [l4/re/util/br\\_manager](#)

## 15.310 L4Re::Util::Br\_manager\_hooks Struct Reference


Predefined server-loop hooks for a server loop using the [Br\\_manager](#).

```
#include <br_manager>
```

Inheritance diagram for L4Re::Util::Br\_manager\_hooks:



Collaboration diagram for L4Re::Util::Br\_manager\_hooks:



### Additional Inherited Members

### Public Types inherited from [L4::ipc\\_svr::Server\\_iface](#)

- typedef [L4::Type\\_info::Demand](#) **Demand**  
*Data type expressing server-side demand for receive buffers.*

### Public Member Functions inherited from [L4Re::Util::Br\\_manager](#)

- **Br\_manager** ()  
*Make a buffer-register (BR) manager.*
- int **alloc\_buffer\_demand** ([Demand](#) const &d) override  
*Tells the server to allocate buffers for the given demand.*
- [L4::Cap](#)< void > **get\_rcv\_cap** (int i) const override  
*Get capability slot allocated to the given receive buffer.*
- int **realloc\_rcv\_cap** (int i) override  
*Allocate a new capability for the given receive buffer.*
- void **set\_rcv\_cap\_flags** (unsigned long flags)  
*Set the receive flags for the buffers.*

- int **add\_timeout** ([L4::lpc\\_svr::Timeout](#) \*, [l4\\_kernel\\_clock\\_t](#)) override  
*No timeouts handled by us.*
- int **remove\_timeout** ([L4::lpc\\_svr::Timeout](#) \*) override  
*No timeouts handled by us.*
- void **setup\_wait** ([l4\\_utcb\\_t](#) \*utcb, [L4::lpc\\_svr::Reply\\_mode](#))  
*[setup\\_wait\(\)](#) used the server loop ([L4::Server](#))*

## Public Member Functions inherited from [L4::lpc\\_svr::Server\\_iface](#)

- **Server\_iface** ()  
*Make a server interface.*
- template<typename T>  
[L4::Cap](#)< T > **rcv\_cap** (int index) const  
*Get given receive buffer as typed capability.*
- [L4::Cap](#)< void > **rcv\_cap** (int index) const  
*Get receive cap with the given index as generic (void) type.*

## Protected Member Functions inherited from [L4Re::Util::Br\\_manager](#)

- unsigned **first\_free\_br** () const  
*Used for assigning BRs for a timeout.*

### 15.310.1 Detailed Description

Predefined server-loop hooks for a server loop using the [Br\\_manager](#).

This class can be used whenever a server loop including full management of receive buffer resources is needed.

Definition at line 165 of file [br\\_manager](#).

The documentation for this struct was generated from the following file:


- [l4/re/util/br\\_manager](#)

## 15.311 [L4Re::Util::Br\\_manager\\_timeout\\_hooks](#) Struct Reference


Predefined server-loop hooks for a server with using the [Br\\_manager](#) and a timeout queue.

```
#include <br_manager>
```

Inheritance diagram for L4Re::Util::Br\_manager\_timeout\_hooks:



Collaboration diagram for L4Re::Util::Br\_manager\_timeout\_hooks:



### Additional Inherited Members

### Public Types inherited from L4::lpc\_svr::Server\_iface

- typedef L4::Type\_info::Demand Demand  
Data type expressing server-side demand for receive buffers.

**Public Member Functions inherited from****L4::lpc\_svr::Timeout\_queue\_hooks< Br\_manager\_timeout\_hooks, Br\_manager >**

- **l4\_timeout\_t** **timeout** ()  
*get the time for the next timeout*
- void **setup\_wait** (l4\_utcb\_t \*utcb, L4::lpc\_svr::Reply\_mode mode)  
*setup\_wait() for the server loop*
- L4::lpc\_svr::Reply\_mode **before\_reply** (l4\_msgtag\_t, l4\_utcb\_t \*)  
*server loop hook*
- int **add\_timeout** (Timeout \*timeout, l4\_kernel\_clock\_t time) override  
*Add a timeout to the queue for time time.*
- int **remove\_timeout** (Timeout \*timeout) override  
*Remove timeout from the queue.*

**Public Member Functions inherited from L4::lpc\_svr::Server\_iface**

- **Server\_iface** ()  
*Make a server interface.*
- virtual int **alloc\_buffer\_demand** (Demand const &demand)=0  
*Tells the server to allocate buffers for the given demand.*
- virtual L4::Cap< void > **get\_rcv\_cap** (int index) const =0  
*Get capability slot allocated to the given receive buffer.*
- virtual int **realloc\_rcv\_cap** (int index)=0  
*Allocate a new capability for the given receive buffer.*
- template<typename T>  
L4::Cap< T > **rcv\_cap** (int index) const  
*Get given receive buffer as typed capability.*
- L4::Cap< void > **rcv\_cap** (int index) const  
*Get receive cap with the given index as generic (void) type.*

**Data Fields inherited from****L4::lpc\_svr::Timeout\_queue\_hooks< Br\_manager\_timeout\_hooks, Br\_manager >**

- **Timeout\_queue** **queue**  
*Use this timeout queue.*

**15.311.1 Detailed Description**

Predefined server-loop hooks for a server with using the [Br\\_manager](#) and a timeout queue.

This class can be used for server loops that need the full package of buffer-register management and a timeout queue.

Definition at line 179 of file [br\\_manager](#).

The documentation for this struct was generated from the following file:

- l4/re/util/br\_manager

## 15.312 L4Re::Util::Cap\_alloc\_base Class Reference

Capability allocator.

```
#include <bitmap_cap_alloc>
```

Collaboration diagram for L4Re::Util::Cap\_alloc\_base:

L4Re::Util::Cap_alloc_base	
+	alloc()
+	free()

### Public Member Functions

- template<typename T>  
[L4::Cap](#)< T > **alloc** () noexcept  
*Allocate a capability slot.*
- template<typename T>  
void **free** ([L4::Cap](#)< T > const &cap, [l4\\_cap\\_idx\\_t](#) task=[L4\\_INVALID\\_CAP](#), [l4\\_umword\\_t](#) unmap\_↔  
flags=[L4\\_FP\\_ALL\\_SPACES](#)) noexcept  
*Free a capability slot.*

### 15.312.1 Detailed Description

Capability allocator.

Definition at line 28 of file [bitmap\\_cap\\_alloc](#).

The documentation for this class was generated from the following file:

- [l4/re/util/bitmap\\_cap\\_alloc](#)




## 15.313 L4Re::Util::Counter< COUNTER > Struct Template Reference

[Counter](#) for [Counting\\_cap\\_alloc](#) with variable data width.

```
#include <counting_cap_alloc>
```

Collaboration diagram for L4Re::Util::Counter< COUNTER >:



### Public Member Functions

- bool [inc](#) ()  
*Increment counter if not yet saturated.*
- Type [dec](#) ()  
*Decrement counter if not saturated.*

### 15.313.1 Detailed Description

```
template<typename COUNTER = unsigned char>
struct L4Re::Util::Counter< COUNTER >
```

[Counter](#) for [Counting\\_cap\\_alloc](#) with variable data width.

This version is not thread safe.

Definition at line 27 of file [counting\\_cap\\_alloc](#).

### 15.313.2 Member Function Documentation

#### 15.313.2.1 dec()

```
template<typename COUNTER = unsigned char>
Type L4Re::Util::Counter< COUNTER >::dec () [inline]
```

Decrement counter if not saturated.

Once the counter reached the saturated state, the counter value isn't changed.

Definition at line 67 of file [counting\\_cap\\_alloc](#).

### 15.313.2.2 inc()

```
template<typename COUNTER = unsigned char>
bool L4Re::Util::Counter< COUNTER >::inc () [inline]
```

Increment counter if not yet saturated.

Once the counter reached the saturated state, the counter value isn't changed.

#### Return values

<i>false</i>	The counter just went saturated after it was increased.
<i>true</i>	Either the counter was already saturated – in that case the counter value was not changed, or the counter was not saturated – in that case the counter was increased.

Definition at line 50 of file [counting\\_cap\\_alloc](#).

The documentation for this struct was generated from the following file:


- [l4/re/util/counting\\_cap\\_alloc](#)

## 15.314 L4Re::Util::Counter\_atomic< COUNTER > Struct Template Reference

Thread safe version of counter for [Counting\\_cap\\_alloc](#).

```
#include <counting_cap_alloc>
```

Collaboration diagram for L4Re::Util::Counter\_atomic< COUNTER >:



#### Public Member Functions

- bool [inc](#) ()  
*Increment counter if not yet saturated.*
- Type [dec](#) ()  
*Decrement counter if not saturated.*

### 15.314.1 Detailed Description

```
template<typename COUNTER = unsigned char>
struct L4Re::Util::Counter_atomic< COUNTER >
```

Thread safe version of counter for [Counting\\_cap\\_alloc](#).

Despite using atomic instructions, this version has to make sure that capability slots are not reused too early. If the last reference is gone, the capability slot has to be unmapped. The slot must only be allocated again when the unmap has completed. This is accomplished by starting with an initial count of 2. The last reference will decrease the counter to 1. Only then, after the slot was unmapped, will the counter be set to 0. This will allow other threads to reallocate the slot.

Definition at line 98 of file [counting\\_cap\\_alloc](#).

### 15.314.2 Member Function Documentation

#### 15.314.2.1 dec()

```
template<typename COUNTER = unsigned char>
Type L4Re::Util::Counter_atomic< COUNTER >::dec () [inline]
```

Decrement counter if not saturated.

Once the counter reached the saturated state, the counter value isn't changed.

Definition at line 142 of file [counting\\_cap\\_alloc](#).

#### 15.314.2.2 inc()

```
template<typename COUNTER = unsigned char>
bool L4Re::Util::Counter_atomic< COUNTER >::inc () [inline]
```

Increment counter if not yet saturated.

Once the counter reached the saturated state, the counter value isn't changed.

#### Return values

<i>false</i>	The counter just went saturated after it was increased.
<i>true</i>	Either the counter was already saturated – in that case the counter value was not changed, or the counter was not saturated – in that case the counter was increased.

Definition at line 121 of file [counting\\_cap\\_alloc](#).

The documentation for this struct was generated from the following file:

- [l4/re/util/counting\\_cap\\_alloc](#)

## 15.315 L4Re::Util::Counting\_cap\_alloc< COUNTERTYPE, Dbg > Class Template Reference

Internal reference-counting cap allocator.

```
#include <counting_cap_alloc>
```

Collaboration diagram for L4Re::Util::Counting\_cap\_alloc< COUNTERTYPE, Dbg >:

L4Re::Util::Counting _cap_alloc< COUNTERTYPE, Dbg >
<ul style="list-style-type: none"> <li>+ alloc()</li> <li>+ alloc()</li> <li>+ take()</li> <li>+ free()</li> <li>+ release()</li> <li>+ last()</li> <li># Counting_cap_alloc()</li> <li># setup()</li> </ul>

### Public Member Functions

- [L4::Cap](#)< void > [alloc](#) () noexcept  
*Allocate a new capability slot.*
- [template](#)<typename T>  
[L4::Cap](#)< T > [alloc](#) () noexcept  
*Allocate a new capability slot.*
- void [take](#) ([L4::Cap](#)< void > cap) noexcept  
*Increase the reference counter for the capability.*
- bool [free](#) ([L4::Cap](#)< void > cap, [l4\\_cap\\_idx\\_t](#) task=[L4\\_INVALID\\_CAP](#), unsigned unmap\_flags=[L4\\_FP\\_ALL\\_SPACES](#)) noexcept  
*Free the capability.*
- bool [release](#) ([L4::Cap](#)< void > cap, [l4\\_cap\\_idx\\_t](#) task=[L4\\_INVALID\\_CAP](#), unsigned unmap\_↔ flags=[L4\\_FP\\_ALL\\_SPACES](#)) noexcept  
*Decrease the reference counter for a capability.*
- long [last](#) () noexcept  
*Return highest capability id managed by this allocator.*

## Protected Member Functions

- [Counting\\_cap\\_alloc](#) () noexcept  
*Create a new, empty allocator.*
- void [setup](#) (void \*m, long capacity, long bias, Dbg \*dbg) noexcept  
*Set up the backing memory for the allocator and the area of managed capability slots.*

### 15.315.1 Detailed Description

```
template<typename COUNTERTYPE, typename Dbg>
class L4Re::Util::Counting_cap_alloc< COUNTERTYPE, Dbg >
```

Internal reference-counting cap allocator.

This is intended for internal use only. [L4Re](#) applications should use [L4Re::Util::cap\\_alloc\(\)](#).

Allocator for capability slots that automatically frees the slot and optionally unmaps the capability when the reference count goes down to zero. Reference counting must be done manually via [take\(\)](#) and [release\(\)](#). The backing store for the reference counters must be provided in the [setup\(\)](#) method. The allocator can recognize capability slots that are not managed by itself and does nothing on such slots.

#### Note

The user must ensure that the backing store is zero-initialized.

The user must ensure that the capability slots managed by this allocator are not used by a different allocator, see [setup\(\)](#).

The operations in this class are not thread-safe.

Definition at line 191 of file [counting\\_cap\\_alloc](#).

### 15.315.2 Constructor & Destructor Documentation

#### 15.315.2.1 Counting\_cap\_alloc()

```
template<typename COUNTERTYPE, typename Dbg>
L4Re::Util::Counting_cap_alloc< COUNTERTYPE, Dbg >::Counting_cap_alloc () [inline], [protected],
[noexcept]
```

Create a new, empty allocator.

Needs to be initialized with [setup\(\)](#) before it can be used.

Definition at line 224 of file [counting\\_cap\\_alloc](#).

### 15.315.3 Member Function Documentation

#### 15.315.3.1 `alloc()` [1/2]

```
template<typename COUNTERTYPE, typename Dbg>
template<typename T>
L4::Cap< T > L4Re::Util::Counting_cap_alloc< COUNTERTYPE, Dbg >::alloc () [inline], [noexcept]
```

Allocate a new capability slot.


##### Returns

The newly allocated capability slot, invalid if the allocator was exhausted.

Definition at line 282 of file [counting\\_cap\\_alloc](#).

References [alloc\(\)](#), and [L4::cap\\_cast\(\)](#).

Here is the call graph for this function:



#### 15.315.3.2 `alloc()` [2/2]

```
template<typename COUNTERTYPE, typename Dbg>
L4::Cap< void > L4Re::Util::Counting_cap_alloc< COUNTERTYPE, Dbg >::alloc () [inline], [noexcept]
```

Allocate a new capability slot.

**Returns**


The newly allocated capability slot, invalid if the allocator was exhausted.

Definition at line 257 of file [counting\\_cap\\_alloc](#).

References [L4::Cap\\_base::Invalid](#), and [L4\\_CAP\\_SHIFT](#).

Referenced by [alloc\(\)](#).

Here is the caller graph for this function:

**15.315.3.3 free()**

```

template<typename COUNTERTYPE, typename Dbg>
bool L4Re::Util::Counting_cap_alloc< COUNTERTYPE, Dbg >::free (
    L4::Cap< void > cap,
    l4_cap_idx_t task = L4_INVALID_CAP,
    unsigned unmap_flags = L4_FP_ALL_SPACES) [inline], [noexcept]
  
```

Free the capability.

**Parameters**

<i>cap</i>	Capability to free.
<i>task</i>	If set, task to unmap the capability from.
<i>unmap_flags</i>	Flags for unmap, see <a href="#">l4_unmap_flags_t</a> .

**Precondition**

The capability has been allocated. Calling free twice on a capability managed by this allocator results in undefined behaviour.


**Returns**

True, if the capability was managed by this allocator.

Definition at line 321 of file [counting\\_cap\\_alloc](#).

References [l4\\_assert](#), [L4Re::Util::L4\\_FP\\_ALL\\_SPACES](#), [L4\\_INVALID\\_CAP](#), [l4\\_is\\_valid\\_cap\(\)](#), and [l4\\_task\\_unmap\(\)](#).

Here is the call graph for this function:

**15.315.3.4 release()**

```

template<typename COUNTERTYPE, typename Dbg>
bool L4Re::Util::Counting_cap_alloc< COUNTERTYPE, Dbg >::release (
    L4::Cap< void > cap,
    l4_cap_idx_t task = L4_INVALID_CAP,
    unsigned unmap_flags = L4_FP_ALL_SPACES) [inline], [noexcept]

```

Decrease the reference counter for a capability.

**Parameters**

<i>cap</i>	Capability to release.
<i>task</i>	If set, task to unmap the capability from.
<i>unmap_flags</i>	Flags for unmap, see <a href="#">l4_unmap_flags_t</a> .

**Precondition**

The capability has been allocated. Calling `release` on a free capability results in undefined behaviour.

**Returns**

True, if the capability was freed as a result of this operation. If false is returned the capability is either still in use or is not managed by this allocator.




Does nothing apart from returning false if the capability is not managed by this allocator.

Definition at line 359 of file [counting\\_cap\\_alloc](#).

References [l4\\_assert](#), [L4Re::Util::L4\\_FP\\_ALL\\_SPACES](#), [L4\\_INVALID\\_CAP](#), and [l4\\_task\\_unmap\(\)](#).

Here is the call graph for this function:



### 15.315.3.5 setup()

```

template<typename COUNTERTYPE, typename Dbg>
void L4Re::Util::Counting_cap_alloc< COUNTERTYPE, Dbg >::setup (
    void * m,
    long capacity,
    long bias,
    Dbg * dbg) [inline], [protected], [noexcept]
  
```

Set up the backing memory for the allocator and the area of managed capability slots.

#### Parameters

<i>m</i>	Pointer to backing memory.
<i>capacity</i>	Number of capabilities that can be stored.
<i>bias</i>	First capability id to use by this allocator.
<i>dbg</i>	Logger for warnings if counter got saturated.

The allocator will manage the capability slots between `bias` and `bias + capacity - 1` (inclusive). It is the responsibility of the user to ensure that these slots are not used otherwise.

Definition at line 242 of file [counting\\_cap\\_alloc](#).

### 15.315.3.6 take()

```

template<typename COUNTERTYPE, typename Dbg>
void L4Re::Util::Counting_cap_alloc< COUNTERTYPE, Dbg >::take (
    L4::Cap< void > cap) [inline], [noexcept]
  
```

Increase the reference counter for the capability.

**Parameters**

<i>cap</i>	Capability, whose reference counter should be increased.
------------	--

If the capability was still free, it will be automatically allocated. Silently does nothing if the capability is not managed by this allocator.

Definition at line 296 of file [counting\\_cap\\_alloc](#).

References [L4\\_CAP\\_SHIFT](#), and [L4\\_UNLIKELY](#).

The documentation for this class was generated from the following file:

- [l4/re/util/counting\\_cap\\_alloc](#)

## 15.316 L4Re::Util::Dataspace\_svr Class Reference

[Dataspace](#) server class.

```
#include <dataspace_svr>
```

Collaboration diagram for L4Re::Util::Dataspace\_svr:

L4Re::Util::Dataspace_svr
<ul style="list-style-type: none"> <li>+ map()</li> <li>+ map_hook()</li> <li>+ take()</li> <li>+ release()</li> <li>+ copy()</li> <li>+ clear()</li> <li>+ allocate()</li> <li>+ page_shift()</li> <li>+ is_static()</li> <li>+ map_info()</li> </ul>

## Public Member Functions

- [l4\\_ret\\_t map](#) (Dataspace::Offset offset, Dataspace::Map\_addr local\_addr, Dataspace::Flags flags, Dataspace::Map\_addr min\_addr, Dataspace::Map\_addr max\_addr, [L4::lpc::Snd\\_fpage](#) &memory)  
*Map a region of the dataspace.*
- virtual [l4\\_ret\\_t map\\_hook](#) (Dataspace::Offset offs, unsigned order, Dataspace::Flags flags, Dataspace::Map\_addr \*base, unsigned \*send\_order)  
*A hook that is called for acquiring the data to be mapped.*
- virtual void [take](#) () noexcept  
*Take a reference to this dataspace.*
- virtual unsigned long [release](#) () noexcept  
*Release a reference to this dataspace.*
- virtual [l4\\_ret\\_t copy](#) ([l4\\_addr\\_t](#) dst\_offs, [l4\\_umword\\_t](#) src\_id, [l4\\_addr\\_t](#) src\_offs, unsigned long size) noexcept  
*Copy from src dataspace to this destination dataspace.*
- virtual [l4\\_ret\\_t clear](#) (unsigned long offs, unsigned long size) const noexcept  
*Clear a region in the dataspace.*
- virtual [l4\\_ret\\_t allocate](#) ([l4\\_addr\\_t](#) offset, [l4\\_size\\_t](#) size, unsigned access) noexcept  
*Allocate a region within a dataspace.*
- virtual unsigned long [page\\_shift](#) () const noexcept  
*Define the size of the flexpage to map.*
- virtual bool [is\\_static](#) () const noexcept  
*Return whether the dataspace is static.*
- virtual [l4\\_ret\\_t map\\_info](#) ([l4\\_addr\\_t](#) &start\_addr, [l4\\_addr\\_t](#) &end\_addr) noexcept  
*Return mapping information for no-MMU systems.*

### 15.316.1 Detailed Description

[Dataspace](#) server class.

The default implementation of the interface provides a continuous dataspace with contiguous pages.

Definition at line 29 of file [dataspace\\_svr](#).

### 15.316.2 Member Function Documentation

#### 15.316.2.1 allocate()

```
virtual l4\_ret\_t L4Re::Util::Dataspace_svr::allocate (  
    l4\_addr\_t offset,  
    l4\_size\_t size,  
    unsigned access) [inline], [virtual], [noexcept]
```

Allocate a region within a dataspace.

#### Parameters

<i>offset</i>	Offset in the dataspace, in bytes.
<i>size</i>	Size of the range, in bytes.

<i>access</i>	Access mode with which the memory backing the dataspace region should be allocated.
---------------	---

#### Return values

0	Success
<0	Error

Definition at line 224 of file [dataspace\\_svr](#).

References [L4\\_ENODEV](#).

#### 15.316.2.2 clear()

```
virtual l4_ret_t L4Re::Util::Dataspace_svr::clear (  
    unsigned long offs,  
    unsigned long size) const [inline], [virtual], [noexcept]
```

Clear a region in the dataspace.

#### Parameters

<i>offs</i>	Start of the region
<i>size</i>	Size of the region

#### Return values

0	Success
<0	Error

Definition at line 192 of file [dataspace\\_svr](#).

References [L4\\_ERANGE](#).

#### 15.316.2.3 copy()

```
virtual l4_ret_t L4Re::Util::Dataspace_svr::copy (  
    l4_addr_t dst_offs,  
    l4_umword_t src_id,  
    l4_addr_t src_offs,  
    unsigned long size) [inline], [virtual], [noexcept]
```

Copy from src dataspace to this destination dataspace.

**Parameters**

<i>dst_offs</i>	Offset into the destination dataspace
<i>src_id</i>	Local id of the source dataspace
<i>src_offs</i>	Offset into the source dataspace
<i>size</i>	Number of bytes to copy

**Return values**

$\geq 0$	Number of bytes copied
$< 0$	An error occurred. The error code may depend on the implementation.

Definition at line 175 of file [dataspace\\_svr](#).

References [L4\\_ENODEV](#).

**15.316.2.4 is\_static()**

```
virtual bool L4Re::Util::Dataspace_svr::is_static () const [inline], [virtual], [noexcept]
```

Return whether the dataspace is static.

**Returns**

True if dataspace is static

Definition at line 244 of file [dataspace\\_svr](#).

**15.316.2.5 map()**

```
l4_ret_t L4Re::Util::Dataspace_svr::map (
    Dataspace::Offset offset,
    Dataspace::Map_addr local_addr,
    Dataspace::Flags flags,
    Dataspace::Map_addr min_addr,
    Dataspace::Map_addr max_addr,
    L4::Ipc::Snd_fpage & memory) [inline]
```

Map a region of the dataspace.

**Parameters**

	<i>offset</i>	Offset to start within data space
	<i>local_addr</i>	Local address to map to.
	<i>flags</i>	<a href="#">Dataspace</a> flags, see <a href="#">L4Re::Dataspace::F::Flags</a> .

	<i>min_addr</i>	Defines start of receive window.
	<i>max_addr</i>	Defines end of receive window.
out	<i>memory</i>	Send fpage to map


### Return values

0	Success
<0	Error

Definition at line 57 of file [dataspace\\_svr](#).

References [L4\\_EOK](#), [L4\\_ERANGE](#), [l4\\_fpage\(\)](#), [L4\\_PAGESHIFT](#), [l4\\_round\\_page\(\)](#), [l4\\_trunc\\_page\(\)](#), [l4\\_trunc\\_size\(\)](#), and [map\\_hook\(\)](#).

Here is the call graph for this function:



### 15.316.2.6 map\_hook()

```

virtual l4_ret_t L4Re::Util::Dataspace_svr::map_hook (
    Dataspace::Offset offs,
    unsigned order,
    Dataspace::Flags flags,
    Dataspace::Map_addr * base,
    unsigned * send_order) [inline], [virtual]

```

A hook that is called for acquiring the data to be mapped.

**Parameters**

<i>offs</i>	Offset in dataspace to supply
<i>order</i>	Log2-size of data to supply
<i>flags</i>	Flags for the mapping
<i>base</i>	Start address of the flexpage to be mapped
<i>send_order</i>	Order (log2 of size) of the flexpage to be mapped

**Return values**

$< 0$	Error and the map request will be aborted with that error.
$\geq 0$	Success


**See also**

[map](#)

Definition at line 136 of file [dataspace\\_svr](#).

Referenced by [map\(\)](#).

Here is the caller graph for this function:

**15.316.2.7 map\_info()**

```
virtual l4\_ret\_t L4Re::Util::Dataspace_svr::map_info (
    l4\_addr\_t & start_addr,
    l4\_addr\_t & end_addr) [inline], [virtual], [noexcept]
```

Return mapping information for no-MMU systems.

The method is only called on no-MMU systems. It should return the address of the underlying backing buffer so that the caller might map the dataspace.

The default implementation always returns an error because the derived class must provide the required information.

**See also**

[L4Re::Dataspace::map\\_info\(\)](#)

Definition at line 259 of file [dataspace\\_svr](#).

References [L4\\_EPERM](#).

#### 15.316.2.8 `page_shift()`

```
virtual unsigned long L4Re::Util::Dataspace_svr::page_shift () const [inline], [virtual],  
[noexcept]
```

Define the size of the flexpage to map.

##### Returns

flexpage size

Definition at line 236 of file [dataspace\\_svr](#).

References [L4\\_LOG2\\_PAGESIZE](#).

#### 15.316.2.9 `release()`

```
virtual unsigned long L4Re::Util::Dataspace_svr::release () [inline], [virtual], [noexcept]
```

Release a reference to this dataspace.

##### Returns

Number of references to the dataspace

Default does nothing and returns always zero.

Definition at line 160 of file [dataspace\\_svr](#).

#### 15.316.2.10 `take()`

```
virtual void L4Re::Util::Dataspace_svr::take () [inline], [virtual], [noexcept]
```

Take a reference to this dataspace.

Default does nothing.

Definition at line 150 of file [dataspace\\_svr](#).

The documentation for this class was generated from the following file:

- `l4/re/util/dataspace_svr`




## 15.317 L4Re::Util::Event\_buffer\_consumer\_t< PAYLOAD > Class Template Reference


An event buffer consumer.

```
#include <event_buffer>
```

Inheritance diagram for L4Re::Util::Event\_buffer\_consumer\_t< PAYLOAD >:



Collaboration diagram for L4Re::Util::Event\_buffer\_consumer\_t< PAYLOAD >:



## Public Member Functions

- template<typename CB, typename D>  
void [foreach\\_available\\_event](#) (CB const &cb, D data=D())  
*Call function on every available event.*
- template<typename CB, typename D>  
void [process](#) (L4::Cap< L4::Irq > irq, L4::Cap< L4::Thread > thread, CB const &cb, D data=D())  
*Continuously wait for events and process them.*

**Public Member Functions inherited from [L4Re::Util::Event\\_buffer\\_t< PAYLOAD >](#)**

- void \* [buf](#) () const noexcept  
*Return the buffer.*
- long [attach](#) ([L4::Cap](#)< [L4Re::Dataspace](#) > ds, [L4::Cap](#)< [L4Re::Rm](#) > rm) noexcept  
*Attach event buffer from address space.*
- long [detach](#) ([L4::Cap](#)< [L4Re::Rm](#) > rm) noexcept  
*Detach event buffer from address space.*

**Public Member Functions inherited from [L4Re::Event\\_buffer\\_t< PAYLOAD >](#)**

- Event \* [next](#) () noexcept  
*Next event in buffer.*
- bool [put](#) (Event const &ev) noexcept  
*Put event into buffer at current position.*

**15.317.1 Detailed Description**

template<typename PAYLOAD>  
class L4Re::Util::Event\_buffer\_consumer\_t< PAYLOAD >

An event buffer consumer.

Definition at line 83 of file [event\\_buffer](#).

**15.317.2 Member Function Documentation****15.317.2.1 [foreach\\_available\\_event\(\)](#)**

```
template<typename PAYLOAD>
template<typename CB, typename D>
void L4Re::Util::Event_buffer_consumer_t< PAYLOAD >::foreach_available_event (
    CB const & cb,
    D data = D()) [inline]
```

Call function on every available event.


**Parameters**

<i>cb</i>	Function callback.
<i>data</i>	Data to pass as an argument to the callback.

Definition at line 94 of file [event\\_buffer](#).

Referenced by [L4Re::Util::Event\\_buffer\\_consumer\\_t< Default\\_event\\_payload >::process\(\)](#).

Here is the caller graph for this function:



### 15.317.2.2 process()

```
template<typename PAYLOAD>
template<typename CB, typename D>
void L4Re::Util::Event_buffer_consumer_t< PAYLOAD >::process (
    L4::Cap< L4::Irq > irq,
    L4::Cap< L4::Thread > thread,
    CB const & cb,
    D data = D()) [inline]
```

Continuously wait for events and process them.

#### Parameters

<i>irq</i>	<a href="#">Event</a> signal to wait for.
<i>thread</i>	Thread capability of the thread calling this function.
<i>cb</i>	Callback function that is called for each received event.
<i>data</i>	Data to pass as an argument to the processing callback.

#### Note

This function never returns.

Definition at line 115 of file [event\\_buffer](#).

The documentation for this class was generated from the following file:


- l4/re/util/event\_buffer

## 15.318 L4Re::Util::Event\_buffer\_t< PAYLOAD > Class Template Reference


Event\_buffer utility class.

```
#include <event_buffer>
```

Inheritance diagram for L4Re::Util::Event\_buffer\_t< PAYLOAD >:



Collaboration diagram for L4Re::Util::Event\_buffer\_t< PAYLOAD >:



### Public Member Functions

- void \* `buf()` const noexcept  
*Return the buffer.*
- long `attach` (L4::Cap< L4Re::Dataspace > ds, L4::Cap< L4Re::Rm > rm) noexcept  
*Attach event buffer from address space.*
- long `detach` (L4::Cap< L4Re::Rm > rm) noexcept  
*Detach event buffer from address space.*

### Public Member Functions inherited from L4Re::Event\_buffer\_t< PAYLOAD >

- Event \* `next()` noexcept  
*Next event in buffer.*
- bool `put` (Event const &ev) noexcept  
*Put event into buffer at current position.*

## 15.318.1 Detailed Description

```
template<typename PAYLOAD>
class L4Re::Util::Event_buffer_t< PAYLOAD >
```

Event\_buffer utility class.

Definition at line 25 of file [event\\_buffer](#).

## 15.318.2 Member Function Documentation

### 15.318.2.1 attach()

```
template<typename PAYLOAD>
long L4Re::Util::Event_buffer_t< PAYLOAD >::attach (
    L4::Cap< L4Re::Dataspace > ds,
    L4::Cap< L4Re::Rm > rm) [inline], [noexcept]
```

Attach event buffer from address space.

#### Parameters

<i>ds</i>	<a href="#">Dataspace</a> of the event buffer.
<i>rm</i>	Region manager to attach buffer to.

#### Returns

0 on success, negative error code otherwise.

Definition at line 45 of file [event\\_buffer](#).

### 15.318.2.2 buf()

```
template<typename PAYLOAD>
void * L4Re::Util::Event_buffer_t< PAYLOAD >::buf () const [inline], [noexcept]
```

Return the buffer.

#### Returns

Pointer to the event buffer.

Definition at line 35 of file [event\\_buffer](#).

### 15.318.2.3 detach()

```
template<typename PAYLOAD>
long L4Re::Util::Event_buffer_t< PAYLOAD >::detach (
    L4::Cap< L4Re::Rm > rm) [inline], [noexcept]
```

Detach event buffer from address space.

#### Parameters

<i>rm</i>	Region manager to detach buffer from.
-----------	---------------------------------------

#### Returns

0 on success, negative error code otherwise.

Definition at line 68 of file [event\\_buffer](#).

The documentation for this class was generated from the following file:

- [l4/re/util/event\\_buffer](#)


## 15.319 L4Re::Util::Event\_svr< SVR > Class Template Reference

Convenience wrapper for implementing an event server.

```
#include <event_svr>
```



Collaboration diagram for L4Re::Util::Event\_svr< SVR >:



## Public Member Functions

- `l4_ret_t op_get_buffer` (L4Re::Event::Rights, [L4::ipc::Cap< L4Re::Dataspace >](#) &ds)  
Handle *L4Re::Event* protocol.

### 15.319.1 Detailed Description

```
template<typename SVR>
class L4Re::Util::Event_svr< SVR >
```

Convenience wrapper for implementing an event server.

See also

[L4Re::Event](#), [L4Re::Util::Event\\_t](#)

Definition at line 28 of file [event\\_svr](#).

The documentation for this class was generated from the following file:


- [l4/re/util/event\\_svr](#)

## 15.320 L4Re::Util::Event\_t< PAYLOAD > Class Template Reference


Convenience wrapper for getting access to an event object.

```
#include <event>
```

Inheritance diagram for L4Re::Util::Event\_t< PAYLOAD >:



Collaboration diagram for L4Re::Util::Event\_t< PAYLOAD >:



## Public Types

- enum [Mode](#) { [Mode\\_irq](#) , [Mode\\_polling](#) }  
*Modes of operation.*

## Public Member Functions

- template<typename IRQ\_TYPE>  
int [init](#) (L4::Cap< [L4Re::Event](#) > event, [L4Re::Env](#) const \*env=[L4Re::Env::env\(\)](#), [L4Re::Cap\\_alloc](#) \*ca=&[L4Re::Util::cap\\_alloc](#))  
*Initialise an event object.*
- int [init\\_poll](#) (L4::Cap< [L4Re::Event](#) > event, [L4Re::Env](#) const \*env=[L4Re::Env::env\(\)](#), [L4Re::Cap\\_alloc](#) \*ca=&[L4Re::Util::cap\\_alloc](#))  
*Initialise an event object in polling mode.*
- [L4Re::Event\\_buffer\\_t](#)< [PAYLOAD](#) > & [buffer](#) ()  
*Get event buffer.*
- [L4::Cap](#)< [L4::Triggerable](#) > [irq](#) () const  
*Get event IRQ.*

### 15.320.1 Detailed Description

```
template<typename PAYLOAD>
class L4Re::Util::Event_t< PAYLOAD >
```

Convenience wrapper for getting access to an event object.

After calling [init\(\)](#) the class supplies the event-buffer and the associated IRQ object.

Definition at line [32](#) of file [event](#).

## 15.320.2 Member Enumeration Documentation

### 15.320.2.1 Mode

```
template<typename PAYLOAD>
enum L4Re::Util::Event_t::Mode
```

Modes of operation.

#### Enumerator

Mode_irq	Create an IRQ and attach, to get notifications.
Mode_polling	Do not use an IRQ.

Definition at line 38 of file [event](#).

## 15.320.3 Member Function Documentation

### 15.320.3.1 buffer()

```
template<typename PAYLOAD>
L4Re::Event_buffer_t< PAYLOAD > & L4Re::Util::Event_t< PAYLOAD >::buffer () [inline]
```

Get event buffer.

#### Returns

[Event](#) buffer object.

Definition at line 148 of file [event](#).

### 15.320.3.2 init()

```
template<typename PAYLOAD>
template<typename IRQ_TYPE>
int L4Re::Util::Event_t< PAYLOAD >::init (
    L4::Cap< L4Re::Event > event,
    L4Re::Env const * env = L4Re::Env::env(),
    L4Re::Cap_alloc * ca = &L4Re::Util::cap_alloc) [inline]
```

Initialise an event object.

#### Template Parameters

<i>IRQ_TYPE</i>	Type used for handling notifications from the event provider. This must be derived from <a href="#">L4::Triggerable</a> .
-----------------	---

### Parameters

<i>event</i>	Capability to event.
<i>env</i>	Pointer to L4Re-Environment
<i>ca</i>	Pointer to capability allocator.

### Return values

0	Success
-L4_ENOMEM	No memory to allocate required capabilities.
<0	Other IPC errors.

Definition at line 59 of file [event](#).

#### 15.320.3.3 init\_poll()

```
template<typename PAYLOAD>
int L4Re::Util::Event_t< PAYLOAD >::init_poll (
    L4::Cap< L4Re::Event > event,
    L4Re::Env const * env = L4Re::Env::env(),
    L4Re::Cap_alloc * ca = &L4Re::Util::cap_alloc) [inline]
```

Initialise an event object in polling mode.

### Parameters

<i>event</i>	Capability to event.
<i>env</i>	Pointer to L4Re-Environment
<i>ca</i>	Pointer to capability allocator.

### Return values

0	Success
-L4_ENOMEM	No memory to allocate required capabilities.
<0	Other IPC errors.

Definition at line 112 of file [event](#).

#### 15.320.3.4 irq()

```
template<typename PAYLOAD>
L4::Cap< L4::Triggerable > L4Re::Util::Event_t< PAYLOAD >::irq () const [inline]
```

Get event IRQ.

Returns

[Event](#) IRQ.

Definition at line [155](#) of file [event](#).

The documentation for this class was generated from the following file:


- [l4/re/util/event](#)

## 15.321 L4Re::Util::Item\_alloc\_base Class Reference

Item allocator.

```
#include <item_alloc>
```

Collaboration diagram for L4Re::Util::Item\_alloc\_base:



### 15.321.1 Detailed Description

Item allocator.

Definition at line [27](#) of file [item\\_alloc](#).

The documentation for this class was generated from the following file:


- [l4/re/util/item\\_alloc](#)

## 15.322 L4Re::Util::Names::Name Class Reference


[Name](#) class.

```
#include <name_space_svr>
```

Inheritance diagram for L4Re::Util::Names::Name:



Collaboration diagram for L4Re::Util::Names::Name:



### Additional Inherited Members

### Public Types inherited from `cxx::String`

- typedef char const \* **Index**  
*Character index type.*

### Public Member Functions inherited from `cxx::String`

- **String** (char const \*s) noexcept  
*Initialize from a zero-terminated string.*
- **String** (char const \*s, unsigned long len) noexcept  
*Initialize from a pointer to first character and a length.*
- **String** (char const \*s, char const \*e) noexcept  
*Initialize with start and end pointer.*
- **String** ()  
*Zero-initialize. Create an invalid string.*



- **Index start** () const  
*Pointer to first character.*
- **Index end** () const  
*Pointer to first byte behind the string.*
- int **len** () const  
*Length.*
- void **start** (char const \*s)  
*Set start.*
- void **len** (unsigned long len)  
*Set length.*
- bool **empty** () const  
*Check if the string has length zero.*
- **String head** (**Index end**) const  
*Return prefix up to index.*
- **String head** (unsigned long **end**) const  
*Prefix of length **end**.*
- **String substr** (unsigned long idx, unsigned long **len**=~0UL) const  
*Substring of length **len** starting at **idx**.*
- **String substr** (char const \***start**, unsigned long **len**=0) const  
*Substring of length **len** starting at **start**.*
- template<typename F>  
char const \* **find\_match** (F &&match) const  
*Find matching character. **match** should be a function such as **isspace**.*
- char const \* **find** (char const \*c) const  
*Find character. Return **end()** if not found.*
- char const \* **find** (int c) const  
*Find character. Return **end()** if not found.*
- char const \* **rfind** (char const \*c) const  
*Find right-most character. Return **end()** if not found.*
- **Index starts\_with** (cxx::String const &c) const  
*Check if **c** is a prefix of string.*
- char const \* **find** (int c, char const \*s) const  
*Find character **c** starting at position **s**. Return **end()** if not found.*
- char const \* **find** (char const \*c, char const \*s) const  
*Find character **c** starting at position **s**.*
- char const & **operator[]** (unsigned long idx) const  
*Get character at **idx**.*
- char const & **operator[]** (int idx) const  
*Get character at **idx**.*
- char const & **operator[]** (**Index idx**) const  
*Get character at **idx**.*
- bool **eof** (char const \*s) const  
*Check if pointer **s** points behind string.*
- template<typename INT>  
int **from\_dec** (INT \*v) const  
*Convert decimal string to integer.*
- template<typename INT>  
int **from\_hex** (INT \*v) const  
*Convert hex string to integer.*
- bool **operator==** (**String** const &o) const  
*Equality.*
- bool **operator!=** (**String** const &o) const  
*Inequality.*

### 15.322.1 Detailed Description

[Name](#) class.

Definition at line 28 of file [name\\_space\\_svr](#).

The documentation for this class was generated from the following file:


- [l4/re/util/name\\_space\\_svr](#)

## 15.323 L4Re::Util::Names::Name\_space Class Reference

Abstract server-side implementation of the L4::Namespace interface.

```
#include <name_space_svr>
```

Collaboration diagram for L4Re::Util::Names::Name\_space:



### Public Member Functions

- virtual **~Name\_space** ()

*The destructor of the derived class is responsible for freeing resources.*

## Protected Member Functions

- virtual Entry \* [alloc\\_dynamic\\_entry](#) (Name const &n, unsigned flags)=0  
*Allocate a new entry for the given name.*
- virtual void [free\\_dynamic\\_entry](#) (Entry \*e)=0  
*Free an entry previously allocated with [alloc\\_dynamic\\_entry](#)().*
- virtual [l4\\_ret\\_t](#) [get\\_epiface](#) ([l4\\_umword\\_t](#) data, bool is\_local, [L4::Epiface](#) \*\*lo)=0  
*Return a pointer to the epiface assigned to a given label.*
- virtual [l4\\_ret\\_t](#) [copy\\_receive\\_cap](#) ([L4::Cap](#)< void > \*cap)=0  
*Return the receive capability for permanent use.*
- virtual void [free\\_capability](#) ([L4::Cap](#)< void > cap)=0  
*Free a capability previously acquired with [copy\\_receive\\_cap](#)().*
- virtual void [free\\_epiface](#) ([L4::Epiface](#) \*epiface)=0  
*Free epiface previously acquired with [get\\_epiface](#)().*

## 15.323.1 Detailed Description

Abstract server-side implementation of the [L4::Namespace](#) interface.

### Note

The derived class is responsible for resource management through the provided interfaces. This includes freeing all resources on destruction!

Definition at line [180](#) of file [name\\_space\\_svr](#).

## 15.323.2 Member Function Documentation

### 15.323.2.1 [alloc\\_dynamic\\_entry](#)()

```
virtual Entry * L4Re::Util::Names::Name_space::alloc_dynamic_entry (
    Name const & n,
    unsigned flags) [protected], [pure virtual]
```

Allocate a new entry for the given name.

### Parameters

<i>n</i>	<a href="#">Name</a> of the entry, must be copied.
<i>flags</i>	Entry flags, see <a href="#">Obj::Flags</a> .


**Returns**

A pointer to the newly allocated entry or NULL on error.

This method is called when a new entry was received. It must allocate memory, copy `n` out of the receive buffer and wrap everything in an Entry.

Referenced by [free\\_epiface\(\)](#).

Here is the caller graph for this function:

**15.323.2.2 copy\_receive\_cap()**

```
virtual l4\_ret\_t L4Re::Util::Names::Name_space::copy_receive_cap (
    L4::Cap< void > * cap) [protected], [pure virtual]
```

Return the receive capability for permanent use.

**Parameters**

out	<i>cap</i>	Capability slot with the received capability. Must be permanently available until <a href="#">free_capability()</a> is called.
-----	------------	--

This method is called when a new entry is registered together with a capability mapping. It must decide whether and where to store the capability and return the final capability slot. Typical implementations return the capability slot in the receive window and allocate a new receive window.

**15.323.2.3 free\_capability()**

```
virtual void L4Re::Util::Names::Name_space::free_capability (
    L4::Cap< void > cap) [protected], [pure virtual]
```

Free a capability previously acquired with [copy\\_receive\\_cap\(\)](#).


**Parameters**

in	<i>cap</i>	Capability to free.
----	------------	---------------------

Counterpart of [copy\\_receive\\_cap](#). Free the capability slot when the entry is deleted or changed.

Referenced by [free\\_epiface\(\)](#).

Here is the caller graph for this function:



#### 15.323.2.4 free\_dynamic\_entry()

```
virtual void L4Re::Util::Names::Name_space::free_dynamic_entry (
    Entry * e)    [protected], [pure virtual]
```


Free an entry previously allocated with [alloc\\_dynamic\\_entry\(\)](#).

##### Parameters

<i>e</i>	Entry to free.
----------	----------------

Referenced by [free\\_epiface\(\)](#).

Here is the caller graph for this function:



#### 15.323.2.5 free\_epiface()

```
virtual void L4Re::Util::Names::Name_space::free_epiface (
    L4::Epiface * epiface) [protected], [pure virtual]
```

Free epiface previously acquired with [get\\_epiface\(\)](#).

##### Parameters


in	<i>epiface</i>	Epiface to free.
----	----------------	------------------

Called when an entry that points to an epiface is deleted allowing implementations that hold resources to free them.


References [alloc\\_dynamic\\_entry\(\)](#), [free\\_capability\(\)](#), [free\\_dynamic\\_entry\(\)](#), [free\\_epiface\(\)](#), [L4\\_BASE\\_TASK\\_CAP](#), [L4\\_EEXIST](#), [L4\\_ENOMEM](#), and [L4Re::Namespace::Overwrite](#).

Referenced by [free\\_epiface\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 15.323.2.6 get\_epiface()

```

virtual l4_ret_t L4Re::Util::Names::Name_space::get_epiface (
    l4_umword_t data,
    bool is_local,
    L4::Epiface ** lo) [protected], [pure virtual]
  
```

Return a pointer to the epiface assigned to a given label.

**Parameters**

in	<i>data</i>	Label or in the local case the capability slot of the receiving capability.
in	<i>is_local</i>	If true, a local capability slot was supplied, if false the label of a locally bound IPC gate.
out	<i>lo</i>	Pointer to epiface responsible for the capability.

**Returns**

[L4\\_EOK](#) if a valid interface could be found or an error message otherwise.

This method is called when a new entry is registered and some local ID was received for the capability. In this case, the generic implementation needs to get the epiface in order to get the capability.

The callee must make sure that the epiface remains valid until `free_epiface` is called. In particular, the capability slot must not be reallocated as long as the namespace server holds a reference to the epiface.

The documentation for this class was generated from the following file:


- `l4/re/util/name_space_svr`

## 15.324 L4Re::Util::Object\_registry Class Reference

A registry that manages server objects and their attached IPC gates for a single server loop for a specific thread.


```
#include <object_registry>
```

Inheritance diagram for L4Re::Util::Object\_registry:





Collaboration diagram for L4Re::Util::Object\_registry:



## Public Member Functions

- `Object_registry (L4::lpc_svr::Server_iface *sif)`  
Create a registry for the main thread of the task using the default factory.
- `Object_registry (L4::lpc_svr::Server_iface *sif, L4::Cap< L4::Thread > server, L4::Cap< L4::Factory > factory)`  
Create a registry for arbitrary threads.
- `L4::Cap< void > register_obj (L4::Epiface *o, char const *service)` override  
Register a new server object to a pre-allocated receive endpoint.
- `L4::Cap< void > register_obj (L4::Epiface *o)` override  
Register a new server object on a newly allocated capability.

- `L4::Cap< L4::Irq > register_irq_obj (L4::Epiface *o)` override  
*Register a handler for an interrupt.*
- `L4::Cap< L4::Rcv_endpoint > register_obj (L4::Epiface *o, L4::Cap< L4::Rcv_endpoint > ep)` override  
*Register a handler for an already existing interrupt.*
- `void unregister_obj (L4::Epiface *o, bool unmap=true)` override  
*Remove a server object from the handler list.*

### Additional Inherited Members

### Static Public Member Functions inherited from `L4::Basic_registry`

- static Value \* `find (l4_umword_t label)`  
*Get the server object for an `lpc_gate` label.*
- static `l4_msgtag_t dispatch (l4_msgtag_t tag, l4_umword_t label, l4_utcb_t *utcb)`  
*The dispatch function called by the server loop.*

## 15.324.1 Detailed Description

A registry that manages server objects and their attached IPC gates for a single server loop for a specific thread.

This class manages most of the setup of a server object. If necessary, an IPC gate is created, the specified thread is bound to the IPC gate. Incoming IPC is dispatched to the server object based on the label of the IPC gate.

The object registry is also able to manage IRQ endpoints. They require a different method for the object creation. Otherwise they are handled in the same way as IPC gates: a server object is responsible to process the incoming interrupts.

Definition at line 41 of file `object_registry`.

## 15.324.2 Constructor & Destructor Documentation

### 15.324.2.1 `Object_registry()` [1/2]

```
L4Re::Util::Object_registry::Object_registry (
    L4::Ipc_svr::Server_iface * sif) [inline], [explicit]
```

Create a registry for the main thread of the task using the default factory.

#### Parameters

<code>sif</code>	Server loop interface.
------------------	------------------------

Definition at line 67 of file `object_registry`.

### 15.324.2.2 Object\_registry() [2/2]

```
L4Re::Util::Object_registry::Object_registry (
    L4::Ipc_svr::Server_iface * sif,
    L4::Cap< L4::Thread > server,
    L4::Cap< L4::Factory > factory) [inline]
```

Create a registry for arbitrary threads.

#### Parameters

<i>sif</i>	Server loop interface.
<i>server</i>	Capability to the thread that executes the server objects.
<i>factory</i>	Capability to a factory object capable of creating new IPC gates.

Definition at line 81 of file [object\\_registry](#).

## 15.324.3 Member Function Documentation

### 15.324.3.1 register\_irq\_obj()

```
L4::Cap< L4::Irq > L4Re::Util::Object_registry::register_irq_obj (
    L4::Epiface * o) [inline], [override], [virtual]
```

Register a handler for an interrupt.

#### Parameters

<i>o</i>	Server object that handles IRQs.
----------	----------------------------------

#### Return values

<a href="#">L4::Cap&lt;L4::Irq&gt;</a>	Capability to a new IRQ object on success.
<a href="#">L4::Cap&lt;L4::Irq&gt;::Invalid</a>	The allocation of the IRQ has failed.

The IRQ will be newly allocated using the registry's factory object. The caller must call [unregister\\_obj\(\)](#) to free all resources.

Implements [L4::Registry\\_iface](#).

Definition at line 227 of file [object\\_registry](#).

**15.324.3.2 register\_obj()** [1/3]

```
L4::Cap< void > L4Re::Util::Object_registry::register_obj (
    L4::Epiface * o) [inline], [override], [virtual]
```

Register a new server object on a newly allocated capability.

**Parameters**

<i>o</i>	Server object that handles IPC requests.
----------	--

**Return values**

<i>L4::Cap&lt; void &gt;</i>	A valid capability to a new IPC gate.
<i>L4::Cap&lt; void &gt;::Invalid</i>	The allocation of the IPC gate has failed.

The IPC gate will be allocated using the registry's factory. The caller must call [unregister\\_obj\(\)](#) to free all resources.

Implements [L4::Registry\\_iface](#).

Definition at line 211 of file [object\\_registry](#).

**15.324.3.3 register\_obj()** [2/3]

```
L4::Cap< void > L4Re::Util::Object_registry::register_obj (
    L4::Epiface * o,
    char const * service) [inline], [override], [virtual]
```

Register a new server object to a pre-allocated receive endpoint.

**Parameters**

<i>o</i>	Server object that handles IPC requests.
<i>service</i>	Name of a pre-allocated receive endpoint.

**Return values**

<i>L4::Cap&lt; void &gt;</i>	The capability known as <i>service</i> on success.
<i>L4::Cap&lt; void &gt;::Invalid</i>	No capability with the given name found.

The interface must be freed with [unregister\\_obj\(\)](#) by the caller to unbind the thread from the capability.

Implements [L4::Registry\\_iface](#).

Definition at line 194 of file [object\\_registry](#).

**15.324.3.4 register\_obj()** [3/3]

```
L4::Cap< L4::Rcv_endpoint > L4Re::Util::Object_registry::register_obj (
    L4::Epiface * o,
    L4::Cap< L4::Rcv_endpoint > ep) [inline], [override], [virtual]
```

Register a handler for an already existing interrupt.

**Parameters**

<i>o</i>	Server object that handles the IPC.
<i>ep</i>	Capability to a receive endpoint, may be a hardware or software interrupt or an IPC gate.

**Return values**

<a href="#">L4::Cap&lt;L4::Rcv_endpoint&gt;</a>	Capability <i>ep</i> on success.
<a href="#">L4::Cap&lt;L4::Rcv_endpoint&gt;::Invalid</a>	The IRQ attach operation has failed.

The interface must be freed with [unregister\\_obj\(\)](#) by the caller to unbind the thread from the capability.

Implements [L4::Registry\\_iface](#).

Definition at line 246 of file [object\\_registry](#).

**15.324.3.5 unregister\_obj()**

```
void L4Re::Util::Object_registry::unregister_obj (
    L4::Epiface * o,
    bool unmap = true) [inline], [override], [virtual]
```

Remove a server object from the handler list.

**Parameters**

<i>o</i>	Server object to unbind.
<i>unmap</i>	Specifies if the object capability shall be unmapped (true) or not. The default (true) is to unmap the capability.


The capability used by the server object will be unmapped if *unmap* is true.

Implements [L4::Registry\\_iface](#).

Definition at line 262 of file [object\\_registry](#).

References [L4::Thread::Modify\\_senders::add\(\)](#), [L4Re::Util::cap\\_alloc](#), [L4::Cap\\_base::fpage\(\)](#), [L4::Cap\\_base::Invalid](#), [L4::Cap\\_base::is\\_valid\(\)](#), [L4Re::Util::L4\\_FP\\_ALL\\_SPACES](#), [L4::Epiface::obj\\_cap\(\)](#), and [L4::Epiface::set\\_server\(\)](#).

Here is the call graph for this function:



The documentation for this class was generated from the following file:


- `l4/re/util/object_registry`

## 15.325 L4Re::Util::Ref\_cap< T > Struct Template Reference


Automatic capability that implements automatic free and unmap of the capability selector.

```
#include <cap_alloc>
```

Inheritance diagram for `L4Re::Util::Ref_cap< T >`:



Collaboration diagram for L4Re::Util::Ref\_cap< T >:



### 15.325.1 Detailed Description

```
template<typename T>
struct L4Re::Util::Ref_cap< T >
```

Automatic capability that implements automatic free and unmap of the capability selector.

#### Template Parameters

<i>T</i>	Type of the object that is referred by the capability.
----------	--

This kind of automatic capability implements a counted reference to a capability selector. The capability shall be unmapped and freed when the reference count in the allocator goes to zero.

#### Usage:

```

L4Re::Util::Ref_cap<L4Re::Dataspace>::Cap global_ds_cap;

{
    L4Re::Util::Ref_cap<L4Re::Dataspace>::Cap
    ds_cap(L4Re::Util::cap_alloc.alloc<L4Re::Dataspace>());
    // reference count for the allocated cap selector is now 1

    // use the dataspace cap
    L4Re::chksys(mem_alloc->alloc(4096, ds_cap.get()));

    global_ds_cap = ds_cap;
    // reference count is now 2
    ...
}
// reference count dropped to 1 (ds_cap is no longer existing).
```

Definition at line 142 of file [cap\\_alloc](#).

The documentation for this struct was generated from the following file:


- [l4/re/util/cap\\_alloc](#)

## 15.326 L4Re::Util::Ref\_del\_cap< T > Struct Template Reference

Automatic capability that implements automatic free and unmap+delete of the capability selector.

```
#include <cap_alloc>
```

Collaboration diagram for L4Re::Util::Ref\_del\_cap< T >:



### 15.326.1 Detailed Description

```
template<typename T>
struct L4Re::Util::Ref_del_cap< T >
```

Automatic capability that implements automatic free and unmap+delete of the capability selector.

#### Template Parameters

<i>T</i>	Type of the object that is referred by the capability.
----------	--

This kind of automatic capability implements a counted reference to a capability selector. The capability shall be unmapped and freed when the reference count in the allocator goes to zero. The main difference to [Ref\\_cap](#) is that the unmap is done with the deletion flag enabled and this leads to the deletion of the object if the current task holds appropriate deletion rights.

#### Usage:

```

L4Re::Util::Ref_del_cap<L4Re::Dataspace>::Cap global_ds_cap;

{
    L4Re::Util::Ref_del_cap<L4Re::Dataspace>::Cap
    ds_cap(L4Re::Util::cap_alloc.alloc<L4Re::Dataspace>());
    // reference count for the allocated cap selector is now 1

    // use the dataspace cap
    L4Re::chksys(mem_alloc->alloc(4096, ds_cap.get()));

    global_ds_cap = ds_cap;
    // reference count is now 2
    ...
}
// reference count dropped to 1 (ds_cap is no longer existing).
...
global_ds_cap = L4_INVALID_CAP;
// reference count dropped to 0 (data space shall be deleted).
```

Definition at line 183 of file [cap\\_alloc](#).

The documentation for this struct was generated from the following file:

- [l4/re/util/cap\\_alloc](#)




## 15.327 L4Re::Util::Registry\_server< LOOP\_HOOKS > Class Template Reference


A server loop object which has a [Object\\_registry](#) included.

```
#include <object_registry>
```

Inheritance diagram for L4Re::Util::Registry\_server< LOOP\_HOOKS >:



Collaboration diagram for L4Re::Util::Registry\_server< LOOP\_HOOKS >:



## Public Member Functions

- [Registry\\_server\(\)](#)  
Create a new server loop object for the main thread of the task.
- [Registry\\_server\(l4\\_utcb\\_t \\*, L4::Cap< L4::Thread > server, L4::Cap< L4::Factory > factory\)](#)  
Create a new server loop object for an arbitrary thread and factory.
- [Registry\\_server\(L4::Cap< L4::Thread > server, L4::Cap< L4::Factory > factory\)](#)

- *Create a new server loop object for an arbitrary thread and factory.*
- `Object_registry` const \* **registry** () const  
*Return registry of this server loop.*
- `Object_registry` \* **registry** ()  
*Return registry of this server loop.*
- void `L4_NORETURN` **loop** (`l4_utcb_t` \*utcb=`l4_utcb`())  
*Start the server loop.*
- template<typename Printer>  
void `L4_NORETURN` **loop\_dbg** (Printer printer, `l4_utcb_t` \*utcb=`l4_utcb`())  
*Start the server loop with error printing.*

## Public Member Functions inherited from `L4::Server< L4::lpc_svr::Default_loop_hooks >`

- `Server` (`l4_utcb_t` \*)  
*Initializes the server loop.*
- `L4_NORETURN` void **internal\_loop** (DISPATCH dispatch, `l4_utcb_t` \*)  
*The server loop.*
- `L4_NORETURN` void **loop\_noexc** (R r, `l4_utcb_t` \*u=`l4_utcb`())  
*Server loop without exception handling.*
- `L4_NORETURN` void **loop** (R r, `l4_utcb_t` \*u=`l4_utcb`())  
*Server loop with internal exception handling.*
- `L4_NORETURN` void **loop\_dbg** (R r, Printer p, `l4_utcb_t` \*u=`l4_utcb`())  
*Server loop with internal exception handling including message printing.*

## Public Member Functions inherited from `L4::lpc_svr::Br_manager_no_buffers`

- int **alloc\_buffer\_demand** (Demand const &demand) override  
*Tells the server to allocate buffers for the given demand.*
- `L4::Cap< void >` **get\_rcv\_cap** (int) const override  
*Returns `L4::Cap<void>::Invalid`, we have no buffer management.*
- int **realloc\_rcv\_cap** (int) override  
*Returns `-L4_ENOMEM`, we have no buffer management.*
- int **add\_timeout** (Timeout \*, `l4_kernel_clock_t`) override  
*Returns `-L4_ENOSYS`, we have no timeout queue.*
- int **remove\_timeout** (Timeout \*) override  
*Returns `-L4_ENOSYS`, we have no timeout queue.*

## Public Member Functions inherited from `L4::lpc_svr::Server_iface`

- `Server_iface` ()  
*Make a server interface.*
- template<typename T>  
`L4::Cap< T >` **rcv\_cap** (int index) const  
*Get given receive buffer as typed capability.*
- `L4::Cap< void >` **rcv\_cap** (int index) const  
*Get receive cap with the given index as generic (void) type.*

## Additional Inherited Members

### Public Types inherited from [L4::lpc\\_svr::Server\\_iface](#)

- typedef [L4::Type\\_info::Demand](#) **Demand**  
*Data type expressing server-side demand for receive buffers.*

### Protected Member Functions inherited from [L4::Server< L4::lpc\\_svr::Default\\_loop\\_hooks >](#)

- [l4\\_msgtag\\_t](#) **reply\_n\_wait** ([l4\\_msgtag\\_t](#) reply, [l4\\_umword\\_t](#) \*p, [l4\\_utcb\\_t](#) \*)  
*Internal implementation for reply and wait.*

### Protected Member Functions inherited from [L4::lpc\\_svr::Br\\_manager\\_no\\_buffers](#)

- unsigned **first\_free\_br** () const  
*Returns 1 as first free buffer.*
- void **setup\_wait** ([l4\\_utcb\\_t](#) \*utcb, [L4::lpc\\_svr::Reply\\_mode](#))  
*Setup wait function for the server loop ([Server<>](#)).*

## 15.327.1 Detailed Description

```
template<typename LOOP_HOOKS = L4::lpc_svr::Default_loop_hooks>
class L4Re::Util::Registry_server< LOOP_HOOKS >
```

A server loop object which has a [Object\\_registry](#) included.

### Examples

[examples/clntsrv/src/server.cc](#), [examples/libs/l4re/c++/shared\\_ds/ds\\_srv.cc](#), and [examples/libs/l4re/streammap/server.cc](#).

Definition at line 293 of file [object\\_registry](#).

## 15.327.2 Constructor & Destructor Documentation

### 15.327.2.1 Registry\_server() [1/3]

```
template<typename LOOP_HOOKS = L4::lpc_svr::Default_loop_hooks>
L4Re::Util::Registry_server< LOOP_HOOKS >::Registry_server () [inline]
```

Create a new server loop object for the main thread of the task.

### Precondition

Must be called from the main thread or behaviour is undefined.

Definition at line 305 of file [object\\_registry](#).

**15.327.2.2 Registry\_server()** [2/3]

```
template<typename LOOP_HOOKS = L4::Ipc_svr::Default_loop_hooks>
L4Re::Util::Registry_server< LOOP_HOOKS >::Registry_server (
    l4_utcb_t * ,
    L4::Cap< L4::Thread > server,
    L4::Cap< L4::Factory > factory) [inline]
```

Create a new server loop object for an arbitrary thread and factory.

**Parameters**

<i>server</i>	Capability to thread running the server loop.
<i>factory</i>	Capability to factory object used to create new IPC gates.

**Deprecated** Note that this variant of the constructor is deprecated, please do not supply the UTCB pointer, it's not used.

Definition at line 317 of file [object\\_registry](#).

**15.327.2.3 Registry\_server()** [3/3]

```
template<typename LOOP_HOOKS = L4::Ipc_svr::Default_loop_hooks>
L4Re::Util::Registry_server< LOOP_HOOKS >::Registry_server (
    L4::Cap< L4::Thread > server,
    L4::Cap< L4::Factory > factory) [inline]
```

Create a new server loop object for an arbitrary thread and factory.

**Parameters**

<i>server</i>	Capability to thread running the server loop.
<i>factory</i>	Capability to factory object used to create new IPC gates.

Definition at line 328 of file [object\\_registry](#).

**15.327.3 Member Function Documentation****15.327.3.1 loop()**

```
template<typename LOOP_HOOKS = L4::Ipc_svr::Default_loop_hooks>
void L4_NORETURN L4Re::Util::Registry_server< LOOP_HOOKS >::loop (
    l4_utcb_t * utcb = l4_utcb()) [inline]
```

Start the server loop.

**Parameters**

<i>utcb</i>	The UTCB of the thread running the server loop, defaults to <a href="#">l4_utcb()</a> .
-------------	---

Definition at line 344 of file [object\\_registry](#).

References [L4\\_NORETURN](#), and [loop\(\)](#).

Referenced by [loop\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 15.327.3.2 `loop_dbg()`

```

template<typename LOOP_HOOKS = L4::Ipc_svr::Default_loop_hooks>
template<typename Printer>
void L4\_NORETURN L4Re::Util::Registry_server< LOOP_HOOKS >::loop_dbg (
    Printer printer,
    l4\_utcb\_t * utcb = l4\_utcb\(\)) [inline]
  
```

Start the server loop with error printing.

#### Template Parameters

<i>Printer</i>	The printer type.
----------------	-------------------

**Parameters**

<i>printer</i>	The printer object on which printf() is called.
<i>utcb</i>	The UTCB of the thread running the server loop, defaults to <a href="#">l4_utcb()</a> .

Definition at line 356 of file [object\\_registry](#).

References [L4\\_NORETURN](#), and [loop\\_dbg\(\)](#).

Referenced by [loop\\_dbg\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



The documentation for this class was generated from the following file:


- [l4/re/util/object\\_registry](#)

## 15.328 L4Re::Util::Smart\_cap\_auto< Unmap\_flags > Class Template Reference

Helper for [Unique\\_cap](#) and [Unique\\_del\\_cap](#).

```
#include <cap_alloc>
```

Collaboration diagram for L4Re::Util::Smart\_cap\_auto< Unmap\_flags >:



### Static Public Member Functions

- static void **free** ([L4::Cap\\_base](#) &c)  
*Free the provided capability.*
- static void **invalidate** ([L4::Cap\\_base](#) &c)  
*Invalidate the provided capability.*

### 15.328.1 Detailed Description

```
template<unsigned long Unmap_flags = L4_FP_ALL_SPACES>
class L4Re::Util::Smart_cap_auto< Unmap_flags >
```

Helper for [Unique\\_cap](#) and [Unique\\_del\\_cap](#).

Definition at line 45 of file [cap\\_alloc](#).

The documentation for this class was generated from the following file:

- [l4/re/util/cap\\_alloc](#)


## 15.329 L4Re::Util::Smart\_count\_cap< Unmap\_flags > Class Template Reference

Helper for [Ref\\_cap](#) and [Ref\\_del\\_cap](#).

```
#include <cap_alloc>
```



Collaboration diagram for L4Re::Util::Smart\_count\_cap< Unmap\_flags >:



### Static Public Member Functions

- static void **free** ([L4::Cap\\_base](#) &c) noexcept  
*Free operation for [L4::Smart\\_cap](#) (decrement ref count and delete if 0).*
- static void **invalidate** ([L4::Cap\\_base](#) &c) noexcept  
*Invalidate operation for [L4::Smart\\_cap](#).*
- static [L4::Cap\\_base](#) **copy** ([L4::Cap\\_base](#) const &src)  
*Copy operation for [L4::Smart\\_cap](#) (increment ref count).*

### 15.329.1 Detailed Description

```
template<unsigned long Unmap_flags = L4_FP_ALL_SPACES>
class L4Re::Util::Smart_count_cap< Unmap_flags >
```

Helper for [Ref\\_cap](#) and [Ref\\_del\\_cap](#).

Definition at line 76 of file [cap\\_alloc](#).

The documentation for this class was generated from the following file:


- [l4/re/util/cap\\_alloc](#)

## 15.330 L4Re::Util::Vcon\_svr< SVR > Class Template Reference

[Console](#) server template class.

```
#include <vcon_svr>
```

Collaboration diagram for L4Re::Util::Vcon\_svr< SVR >:



### 15.330.1 Detailed Description

```
template<typename SVR>
class L4Re::Util::Vcon_svr< SVR >
```

[Console](#) server template class.

This template uses `vcon_write()` and `vcon_read()` to get and deliver data from the implementor.

`vcon_read()` needs to update the status argument with the `L4_vcon_read_stat` flags, especially the `L4_VCON_READ_STAT_DONE` flag to indicate that there's nothing more to read for the other end.

`vcon_write()` gets the live data from the UTCB. Make sure to copy out the data before using the UTCB again.

The size parameter of both functions is given in bytes.

Definition at line [36](#) of file [vcon\\_svr](#).

The documentation for this class was generated from the following file:


- `l4/re/util/vcon_svr`

## 15.331 L4Re::Util::Video::Goos\_svr Class Reference

Goos server class.

```
#include <goos_svr>
```

Collaboration diagram for L4Re::Util::Video::Goos\_svr:



## Public Member Functions

- `L4::Cap< L4Re::Dataspace > get_fb () const`  
*Return framebuffer memory dataspace.*
- `L4Re::Video::Goos::Info const * screen_info () const`  
*Goos information structure.*
- `L4Re::Video::View::Info const * view_info () const`

*View information structure.*

- virtual int [refresh](#) (int x, int y, int w, int h)

*Refresh area of the framebuffer.*

- void [init\\_infos](#) ()

*Initialize the view information structure of this object.*

- virtual [~Goos\\_svr](#) ()

*Destructor.*

## Protected Attributes

- [L4::Cap](#)< [L4Re::Dataspace](#) > [\\_fb\\_ds](#)

*Goos memory dataspace.*

- [L4Re::Video::Goos::Info](#) [\\_screen\\_info](#)

*Goos information.*

- [L4Re::Video::View::Info](#) [\\_view\\_info](#)

*View information.*

## 15.331.1 Detailed Description

Goos server class.

Definition at line 25 of file [goos\\_svr](#).

## 15.331.2 Member Function Documentation

### 15.331.2.1 [get\\_fb\(\)](#)

```
L4::Cap< L4Re::Dataspace > L4Re::Util::Video::Goos_svr::get_fb () const [inline]
```

Return framebuffer memory dataspace.

#### Returns

Goos memory dataspace

Definition at line 42 of file [goos\\_svr](#).

References [\\_fb\\_ds](#).

### 15.331.2.2 [init\\_infos\(\)](#)

```
void L4Re::Util::Video::Goos_svr::init_infos () [inline]
```

Initialize the view information structure of this object.

This function initializes the view info structure of this goos object based on the information in the goos information, i.e. the width, height and pixel\_info of the goos information has to contain valid values before calling [init\\_info\(\)](#).

Definition at line 78 of file [goos\\_svr](#).

References [\\_screen\\_info](#), and [\\_view\\_info](#).

### 15.331.2.3 refresh()

```
virtual int L4Re::Util::Video::Goos_svr::refresh (  
    int x,  
    int y,  
    int w,  
    int h) [inline], [virtual]
```

Refresh area of the framebuffer.

#### Parameters

<i>x</i>	X coordinate (pixels)
<i>y</i>	Y coordinate (pixels)
<i>w</i>	Width of area in pixels
<i>h</i>	Height of area in pixels

#### Returns

0 on success, negative error code otherwise

Definition at line 66 of file [goos\\_svr](#).

References [L4\\_ENOSYS](#).

### 15.331.2.4 screen\_info()

```
L4Re::Video::Goos::Info const * L4Re::Util::Video::Goos_svr::screen_info () const [inline]
```

Goos information structure.

#### Returns

Return goos information structure.

Definition at line 48 of file [goos\\_svr](#).

References [\\_screen\\_info](#).

### 15.331.2.5 view\_info()

```
L4Re::Video::View::Info const * L4Re::Util::Video::Goos_svr::view_info () const [inline]
```

View information structure.

#### Returns

Return view information structure.

Definition at line 54 of file [goos\\_svr](#).

References [\\_view\\_info](#).

The documentation for this class was generated from the following file:


- [l4/re/util/video/goos\\_svr](#)

## 15.332 L4Re::Vfs::Be\_file Class Reference


Boiler plate class for implementing an open file for [L4Re::Vfs](#).

```
#include <backend>
```

Inheritance diagram for L4Re::Vfs::Be\_file:



Collaboration diagram for L4Re::Vfs::Be\_file:



## Public Member Functions

- `int unlock_all_locks ()` noexcept override  
*Unlock all locks on the file.*
- `L4::Cap< L4Re::Dataspace > data_space ()` noexcept override  
*Get an [L4Re::Dataspace](#) object for the file.*
- `ssize_t readv (const struct iovec *, int)` noexcept override  
*Default backend for POSIX read and readv functions.*
- `ssize_t writev (const struct iovec *, int)` noexcept override  
*Default backend for POSIX write and writev functions.*
- `ssize_t pwritev (const struct iovec *, int, off64_t)` noexcept override  
*Default backend for POSIX pwrite and pwritev functions.*
- `ssize_t preadv (const struct iovec *, int, off64_t)` noexcept override  
*Default backend for POSIX pread and preadv functions.*
- `off64_t lseek (off64_t, int)` noexcept override  
*Default backend for POSIX seek and lseek functions.*
- `int ftruncate (off64_t)` noexcept override  
*Default backend for the POSIX truncate, ftruncate and similar functions.*
- `int fsync ()` const noexcept override  
*Default backend for POSIX fsync.*

- int **fdatasync** () const noexcept override  
*Default backend for POSIX fdatasync.*
- int **ioctl** (unsigned long, va\_list) noexcept override  
*Default backend for POSIX ioctl.*
- int **fstat** (struct stat64 \*) const noexcept override  
*Get status information for the file.*
- int **fchmod** (mode\_t) noexcept override  
*Default backend for POSIX chmod and fchmod.*
- int **get\_status\_flags** () const noexcept override  
*Default backend for POSIX fcntl subfunctions.*
- int **set\_status\_flags** (long) noexcept override  
*Default backend for POSIX fcntl subfunctions.*
- int **get\_lock** (struct flock64 \*) noexcept override  
*Default backend for POSIX fcntl subfunctions.*
- int **set\_lock** (struct flock64 \*, bool) noexcept override  
*Default backend for POSIX fcntl subfunctions.*
- int **faccessat** (const char \*, int, int) noexcept override  
*Default backend for POSIX access and faccessat functions.*
- int **fchmodat** (const char \*, mode\_t, int) noexcept override  
*Default backend for POSIX fchmodat function.*
- int **utime** (const struct utimbuf \*) noexcept override  
*Default backend for POSIX utime.*
- int **utimes** (const struct timeval[2]) noexcept override  
*Default backend for POSIX utimes.*
- int **utimensat** (const char \*, const struct timespec[2], int) noexcept override  
*Default backend for POSIX utimensat.*
- int **mkdir** (const char \*, mode\_t) noexcept override  
*Default backend for POSIX mkdir and mkdirat.*
- int **unlink** (const char \*) noexcept override  
*Default backend for POSIX unlink, unlinkat.*
- int **rename** (const char \*, const char \*) noexcept override  
*Default backend for POSIX rename, renameat.*
- int **link** (const char \*, const char \*) noexcept override  
*Default backend for POSIX link, linkat.*
- int **symlink** (const char \*, const char \*) noexcept override  
*Default backend for POSIX symlink, symlinkat.*
- int **rmdir** (const char \*) noexcept override  
*Default backend for POSIX rmdir, rmdirat.*
- ssize\_t **readlink** (char \*, size\_t) override  
*Default backend for POSIX readlink, readlinkat.*
- bool **check\_ready** ([Ready\\_type](#)) noexcept override  
*Default implementation of a readiness check.*

### Additional Inherited Members

### Public Types inherited from [L4Re::Vfs::Generic\\_file](#)

- enum [Ready\\_type](#) : unsigned  
*Type of I/O operation/condition a file can indicate readiness.*



## 15.332.1 Detailed Description

Boiler plate class for implementing an open file for [L4Re::Vfs](#).

This class may be used as a base class for everything that a POSIX file descriptor may point to. This are things such as regular files, directories, special device files, streams, pipes, and so on.

### Examples

[tmpfs/lib/src/fs.cc](#).

Definition at line 30 of file [backend](#).

## 15.332.2 Member Function Documentation

### 15.332.2.1 `check_ready()`

```
bool L4Re::Vfs::Be_file::check_ready (
    Ready_type ) [inline], [override], [virtual], [noexcept]
```

Default implementation of a readiness check.

By default, we assume a file is not ready for an I/O operation/condition since the proper semantics of that relies on the backend.

### Returns

Always false.

Implements [L4Re::Vfs::Generic\\_file](#).

Definition at line 217 of file [backend](#).

### 15.332.2.2 `data_space()`

```
L4::Cap< L4Re::Dataspace > L4Re::Vfs::Be_file::data_space () [inline], [override], [virtual],
[noexcept]
```

Get an [L4Re::Dataspace](#) object for the file.

This is used as a backend for POSIX mmap and mmap2 functions.

### Note

mmap is not possible if the function returns an invalid capability.

### Returns

A capability to an [L4Re::Dataspace](#) that represents the file contents in an [L4Re](#) way.

Implements [L4Re::Vfs::Regular\\_file](#).

Definition at line 47 of file [backend](#).

References [L4::Cap\\_base::Invalid](#).

**15.332.2.3 fstat()**

```
int L4Re::Vfs::Be_file::fstat (
    struct stat64 * buf) const [inline], [override], [virtual], [noexcept]
```

Get status information for the file.

This is the backend for POSIX fstat, stat, fstat64 and friends.

**Parameters**

out	buf	This buffer is filled with the status information.
-----	-----	--

**Returns**

0 on success, or <0 on error.

Implements [L4Re::Vfs::Generic\\_file](#).

Definition at line 86 of file [backend](#).

**15.332.2.4 unlock\_all\_locks()**

```
int L4Re::Vfs::Be_file::unlock_all_locks () [inline], [override], [virtual], [noexcept]
```

Unlock all locks on the file.

**Note**

All locks means all locks independent of which file the locks were taken by.

This method is called by the POSIX close implementation to get the POSIX semantics of releasing all locks taken by this application on a close for any fd referencing the real file.

**Returns**

0 on success, or <0 on error.

Implements [L4Re::Vfs::Generic\\_file](#).

Definition at line 43 of file [backend](#).

The documentation for this class was generated from the following file:


- l4/l4re\_vfs/backend

## 15.333 L4Re::Vfs::Be\_file\_system Class Reference


Boilerplate class for implementing a [L4Re::Vfs::File\\_system](#).

```
#include <backend>
```

Inheritance diagram for L4Re::Vfs::Be\_file\_system:



Collaboration diagram for L4Re::Vfs::Be\_file\_system:



### Public Member Functions

- [Be\\_file\\_system](#) (char const \*fstype) noexcept  
*Create a file-system object for the given fstype.*
- [~Be\\_file\\_system](#) () noexcept  
*Destroy a file-system object.*
- char const \* [type](#) () const noexcept override  
*Return the file-system type.*

### Public Member Functions inherited from L4Re::Vfs::File\_system

- virtual int [mount](#) (char const \*source, unsigned long mountflags, void const \*data, [cxx::Ref\\_ptr](#)< [File](#) > \*dir) noexcept=0  
*Create a directory object dir representing source mounted with this file system.*

## 15.333.1 Detailed Description

Boilerplate class for implementing a [L4Re::Vfs::File\\_system](#).

This class already takes care of registering and unregistering the file system in the global registry and implements the [type\(\)](#) method.

### Examples

[tmpfs/lib/src/fs.cc](#).

Definition at line 310 of file [backend](#).

## 15.333.2 Constructor & Destructor Documentation

### 15.333.2.1 Be\_file\_system()

```
L4Re::Vfs::Be_file_system::Be_file_system (
    char const * fstype) [inline], [explicit], [noexcept]
```

Create a file-system object for the given *fstype*.

#### Parameters

<i>fstype</i>	The type that <a href="#">type()</a> shall return.
---------------	--

This constructor takes care of registering the file system in the registry of L4Re::Vfs::vfs\_ops.

Definition at line 324 of file [backend](#).

### 15.333.2.2 ~Be\_file\_system()

```
L4Re::Vfs::Be_file_system::~~Be_file_system () [inline], [noexcept]
```

Destroy a file-system object.

This destructor takes care of removing this file system from the registry of L4Re::Vfs::vfs\_ops.

Definition at line 336 of file [backend](#).

## 15.333.3 Member Function Documentation

### 15.333.3.1 type()

```
char const * L4Re::Vfs::Be_file_system::type () const [inline], [override], [virtual], [noexcept]
```

Return the file-system type.

Returns the file-system type given as *fstype* in the constructor.

Implements [L4Re::Vfs::File\\_system](#).

Definition at line 346 of file [backend](#).

The documentation for this class was generated from the following file:


- l4/l4re\_vfs/backend

## 15.334 L4Re::Vfs::Directory Class Reference

Interface for a POSIX file that is a directory.

```
#include <vfs.h>
```

Inheritance diagram for L4Re::Vfs::Directory:



Collaboration diagram for L4Re::Vfs::Directory:

L4Re::Vfs::Directory	
+	faccessat()
+	mkdir()
+	unlink()
+	rename()
+	link()
+	symlink()
+	rmdir()

### Public Member Functions

- virtual int [faccessat](#) (const char \*path, int mode, int flags) noexcept=0  
*Check access permissions on the given file.*
- virtual int [mkdir](#) (const char \*path, mode\_t mode) noexcept=0  
*Create a new subdirectory.*
- virtual int [unlink](#) (const char \*path) noexcept=0  
*Unlink the given file from that directory.*
- virtual int [rename](#) (const char \*src\_path, const char \*dst\_path) noexcept=0  
*Rename the given file.*
- virtual int [link](#) (const char \*src\_path, const char \*dst\_path) noexcept=0  
*Create a hard link (second name) for the given file.*
- virtual int [symlink](#) (const char \*src\_path, const char \*dst\_path) noexcept=0  
*Create a symbolic link for the given file.*
- virtual int [rmdir](#) (const char \*path) noexcept=0  
*Delete an empty directory.*

### 15.334.1 Detailed Description

Interface for a POSIX file that is a directory.

This interface provides functionality for directory files in the [L4Re::Vfs](#). However, real objects always use the combined [L4Re::Vfs::File](#) interface.

Definition at line 160 of file [vfs.h](#).

## 15.334.2 Member Function Documentation

### 15.334.2.1 faccessat()

```
virtual int L4Re::Vfs::Directory::faccessat (
    const char * path,
    int mode,
    int flags) [pure virtual], [noexcept]
```

Check access permissions on the given file.

Backend function for POSIX access and faccessat functions.

#### Parameters

<i>path</i>	The path relative to this directory. Note: <i>path</i> is relative to this directory and may contain subdirectories.
<i>mode</i>	The access mode to check.
<i>flags</i>	The flags as in POSIX faccessat (AT_EACCESS, AT_SYMLINK_NOFOLLOW).

#### Returns

0 on success, or <0 on error.

Implemented in [L4Re::Vfs::Be\\_file](#).

### 15.334.2.2 link()

```
virtual int L4Re::Vfs::Directory::link (
    const char * src_path,
    const char * dst_path) [pure virtual], [noexcept]
```

Create a hard link (second name) for the given file.

Backend for the POSIX link and linkat functions.

#### Parameters

<i>src_path</i>	The old name of the file. Note: <i>src_path</i> is relative to this directory and may contain subdirectories.
<i>dst_path</i>	The new (second) name for the file. Note: <i>dst_path</i> is relative to this directory and may contain subdirectories.

#### Returns

0 on success, or <0 on error.

Implemented in [L4Re::Vfs::Be\\_file](#).



### 15.334.2.3 mkdir()

```
virtual int L4Re::Vfs::Directory::mkdir (
    const char * path,
    mode_t mode) [pure virtual], [noexcept]
```

Create a new subdirectory.

Backend for POSIX mkdir and mkdirat function calls.

#### Parameters

<i>path</i>	The name of the subdirectory to create. Note: <i>path</i> is relative to this directory and may contain subdirectories.
<i>mode</i>	The file mode to use for the new directory.

#### Returns

0 on success, or <0 on error. -ENOTDIR if this or some component in path is not a directory.

Implemented in [L4Re::Vfs::Be\\_file](#).

### 15.334.2.4 rename()

```
virtual int L4Re::Vfs::Directory::rename (
    const char * src_path,
    const char * dst_path) [pure virtual], [noexcept]
```

Rename the given file.

Backend for the POSIX rename, renameat functions.

#### Parameters

<i>src_path</i>	The old name of the file to rename. Note: <i>src_path</i> is relative to this directory and may contain subdirectories.
<i>dst_path</i>	The new name for the file. Note: <i>dst_path</i> is relative to this directory and may contain subdirectories.

#### Returns

0 on success, or <0 on error.

Implemented in [L4Re::Vfs::Be\\_file](#).

### 15.334.2.5 rmdir()

```
virtual int L4Re::Vfs::Directory::rmdir (  
    const char * path)    [pure virtual], [noexcept]
```

Delete an empty directory.

Backend for POSIX rmdir, rmdirat functions.

#### Parameters

<i>path</i>	The name of the directory to remove. Note: <i>path</i> is relative to this directory and may contain subdirectories.
-------------	--

#### Returns

0 on success, or <0 on error.

Implemented in [L4Re::Vfs::Be\\_file](#).

### 15.334.2.6 symlink()

```
virtual int L4Re::Vfs::Directory::symlink (  
    const char * src_path,  
    const char * dst_path)    [pure virtual], [noexcept]
```

Create a symbolic link for the given file.

Backend for the POSIX symlink and symlinkat functions.

#### Parameters

<i>src_path</i>	The old name of the file. Note: <i>src_path</i> shall be an absolute path.
<i>dst_path</i>	The name for symlink. Note: <i>dst_path</i> is relative to this directory and may contain subdirectories.

#### Returns

0 on success, or <0 on error.

Implemented in [L4Re::Vfs::Be\\_file](#).

### 15.334.2.7 unlink()

```
virtual int L4Re::Vfs::Directory::unlink (
    const char * path) [pure virtual], [noexcept]
```

Unlink the given file from that directory.

Backend for the POSIX unlink and unlinkat functions.

#### Parameters

<i>path</i>	The name of the file to unlink. Note: <i>path</i> is relative to this directory and may contain subdirectories.
-------------	---

#### Returns

0 on success, or <0 on error.

Implemented in [L4Re::Vfs::Be\\_file](#).

The documentation for this class was generated from the following file:


- l4/l4re\_vfs/vfs.h

## 15.335 L4Re::Vfs::File Class Reference


The basic interface for an open POSIX file.

```
#include <vfs.h>
```

Inheritance diagram for L4Re::Vfs::File:



Collaboration diagram for L4Re::Vfs::File:



## Additional Inherited Members

### Public Types inherited from L4Re::Vfs::Generic\_file

- enum [Ready\\_type](#) : unsigned  
*Type of I/O operation/condition a file can indicate readiness.*

### Public Member Functions inherited from L4Re::Vfs::Generic\_file

- virtual int [unlock\\_all\\_locks](#) () noexcept=0  
*Unlock all locks on the file.*
- virtual int [fstat](#) (struct stat64 \*buf) const noexcept=0  
*Get status information for the file.*
- virtual int [fchmod](#) (mode\_t) noexcept=0  
*Change POSIX access rights on the file.*
- virtual int [get\\_status\\_flags](#) () const noexcept=0  
*Get file status flags (fcntl F\_GETFL).*
- virtual int [set\\_status\\_flags](#) (long flags) noexcept=0  
*Set file status flags (fcntl F\_SETFL).*
- virtual bool [check\\_ready](#) ([Ready\\_type](#) rt) noexcept=0  
*Check whether the file is ready for an I/O operation/condition.*

### Public Member Functions inherited from L4Re::Vfs::Regular\_file

- virtual [L4::Cap](#)< [L4Re::Dataspace](#) > [data\\_space](#) () noexcept=0  
*Get an [L4Re::Dataspace](#) object for the file.*
- virtual ssize\_t [readv](#) (const struct iovec \*, int iovcnt) noexcept=0  
*Read one or more blocks of data from the file.*
- virtual ssize\_t [writev](#) (const struct iovec \*, int iovcnt) noexcept=0  
*Write one or more blocks of data to the file.*
- virtual off64\_t [lseek](#) (off64\_t, int) noexcept=0  
*Change the file pointer.*
- virtual int [ftruncate](#) (off64\_t pos) noexcept=0  
*Truncate the file at the given position.*
- virtual int [fsync](#) () const noexcept=0  
*Sync the data and meta data to persistent storage.*
- virtual int [fdatasync](#) () const noexcept=0  
*Sync the data to persistent storage.*
- virtual int [get\\_lock](#) (struct flock64 \*lock) noexcept=0  
*Test if the given lock can be placed in the file.*
- virtual int [set\\_lock](#) (struct flock64 \*lock, bool wait) noexcept=0  
*Acquire or release the given lock on the file.*

## Public Member Functions inherited from [L4Re::Vfs::Directory](#)

- virtual int [faccessat](#) (const char \*path, int mode, int flags) noexcept=0  
*Check access permissions on the given file.*
- virtual int [mkdir](#) (const char \*path, mode\_t mode) noexcept=0  
*Create a new subdirectory.*
- virtual int [unlink](#) (const char \*path) noexcept=0  
*Unlink the given file from that directory.*
- virtual int [rename](#) (const char \*src\_path, const char \*dst\_path) noexcept=0  
*Rename the given file.*
- virtual int [link](#) (const char \*src\_path, const char \*dst\_path) noexcept=0  
*Create a hard link (second name) for the given file.*
- virtual int [symlink](#) (const char \*src\_path, const char \*dst\_path) noexcept=0  
*Create a symbolic link for the given file.*
- virtual int [rmdir](#) (const char \*path) noexcept=0  
*Delete an empty directory.*

## Public Member Functions inherited from [L4Re::Vfs::Special\\_file](#)

- virtual int [ioctl](#) (unsigned long cmd, va\_list args) noexcept=0  
*The famous IO control.*

### 15.335.1 Detailed Description

The basic interface for an open POSIX file.

An open POSIX file can be anything that hides behind a POSIX file descriptor. This means that even directories are files. An open file can be anything from a directory to a special device file so see [Generic\\_file](#), [Regular\\_file](#), [Directory](#), and [Special\\_file](#) for more information.

#### Note

For implementing a backend for the [L4Re::Vfs](#) [L4Re::Vfs::Be\\_file](#) may be used as a base class.

Definition at line [455](#) of file [vfs.h](#).

The documentation for this class was generated from the following file:


- [l4/l4re\\_vfs/vfs.h](#)

## 15.336 L4Re::Vfs::File\_system Class Reference


Basic interface for an [L4Re::Vfs](#) file system.

```
#include <vfs.h>
```

Inheritance diagram for L4Re::Vfs::File\_system:



Collaboration diagram for L4Re::Vfs::File\_system:



### Public Member Functions

- virtual char const \* `type()` const noexcept=0  
*Returns the type of the file system used in mount as fstype argument.*
- virtual int `mount` (char const \*source, unsigned long mountflags, void const \*data, [cxx::Ref\\_ptr< File >](#) \*dir) noexcept=0  
*Create a directory object dir representing source mounted with this file system.*

### 15.336.1 Detailed Description

Basic interface for an [L4Re::Vfs](#) file system.

#### Note

For implementing a special file system [L4Re::Vfs::Be\\_file\\_system](#) may be used as a base class.

The main purpose of this interface is to have a single object for each supported file-system type (e.g., ext2, vfat) that exists in the application and is registered at the [L4Re::Vfs::Fs](#) singleton available via [L4Re::Vfs::vfs\\_ops](#). Ultimately, the POSIX mount function calls the [File\\_system::mount](#) method matching the file-system type given in mount.

Definition at line 857 of file [vfs.h](#).

### 15.336.2 Member Function Documentation

#### 15.336.2.1 mount()

```
virtual int L4Re::Vfs::File_system::mount (
    char const * source,
    unsigned long mountflags,
    void const * data,
    cxx::Ref_ptr< File > * dir) [pure virtual], [noexcept]
```

Create a directory object *dir* representing *source* mounted with this file system.

#### Parameters

	<i>source</i>	The path to the source device to mount. This may also be some URL or anything file-system specific.
	<i>mountflags</i>	The mount flags as specified in the POSIX mount call.
	<i>data</i>	The data as specified in the POSIX mount call. The contents are file-system specific.
out	<i>dir</i>	A new directory object representing the file-system root directory.

#### Returns

0 on success, and <0 on error (e.g. -EINVAL).

References [mount\(\)](#).

Referenced by [mount\(\)](#).

Here is the call graph for this function:





Here is the caller graph for this function:



### 15.336.2.2 type()

```
virtual char const * L4Re::Vfs::File_system::type () const [pure virtual], [noexcept]
```

Returns the type of the file system used in mount as fstype argument.

#### Note

This method is already provided by [Be\\_file\\_system](#).

Implemented in [L4Re::Vfs::Be\\_file\\_system](#).

The documentation for this class was generated from the following file:


- `l4/l4re_vfs/vfs.h`

## 15.337 L4Re::Vfs::Fs Class Reference

POSIX File-system related functionality.

```
#include <vfs.h>
```

Inheritance diagram for L4Re::Vfs::Fs:



Collaboration diagram for L4Re::Vfs::Fs:

L4Re::Vfs::Fs
<ul style="list-style-type: none"> <li>+ <a href="#">get_file()</a></li> <li>+ <a href="#">get_root()</a></li> <li>+ <a href="#">get_cwd()</a></li> <li>+ <a href="#">set_cwd()</a></li> <li>+ <a href="#">alloc_fd()</a></li> <li>+ <a href="#">set_fd()</a></li> <li>+ <a href="#">free_fd()</a></li> <li>+ <a href="#">mount()</a></li> <li>+ <a href="#">mount()</a></li> </ul>

## Public Member Functions

- virtual [cxx::Ref\\_ptr< File >](#) [get\\_file](#) (int fd) noexcept=0  
*Get the [L4Re::Vfs::File](#) for the file descriptor fd.*
- virtual [cxx::Ref\\_ptr< File >](#) [get\\_root](#) () noexcept=0  
*Get the directory object for the application's root directory.*
- virtual [cxx::Ref\\_ptr< File >](#) [get\\_cwd](#) () noexcept  
*Get the directory object for the application's current working directory.*
- virtual void [set\\_cwd](#) ([cxx::Ref\\_ptr< File >](#) const &) noexcept  
*Set the current working directory for the application.*
- virtual int [alloc\\_fd](#) ([cxx::Ref\\_ptr< File >](#) const &f=[cxx::Ref\\_ptr<>::Nil](#)) noexcept=0  
*Allocate the next free file descriptor.*
- virtual [cxx::Pair< cxx::Ref\\_ptr< File >, int >](#) [set\\_fd](#) (int fd, [cxx::Ref\\_ptr< File >](#) const &f=[cxx::Ref\\_ptr<>::Nil](#)) noexcept=0  
*Set the file object referenced by the file descriptor fd.*
- virtual [cxx::Ref\\_ptr< File >](#) [free\\_fd](#) (int fd) noexcept=0  
*Free the file descriptor fd.*
- virtual int [mount](#) (char const \*path, [cxx::Ref\\_ptr< File >](#) const &dir) noexcept=0  
*Mount a given file object at the given global path in the VFS.*
- int [mount](#) (char const \*source, char const \*target, char const \*fstype, unsigned long mountflags, void const \*data) noexcept  
*Backend for the POSIX mount call.*

### 15.337.1 Detailed Description

POSIX File-system related functionality.

#### Note

This class usually exists as a singleton and as a superclass of [L4Re::Vfs::Ops](#) (

#### See also

[L4Re::Vfs::vfs\\_ops](#)).

Definition at line [946](#) of file [vfs.h](#).

### 15.337.2 Member Function Documentation

#### 15.337.2.1 alloc\_fd()

```
virtual int L4Re::Vfs::Fs::alloc_fd (
    cxx::Ref_ptr< File > const & f = cxx::Ref_ptr<>::Nil) [pure virtual], [noexcept]
```

Allocate the next free file descriptor.

#### Parameters

<i>f</i>	The file to assign to that file descriptor.
----------	---

#### Returns

The allocated file descriptor, or -EMFILE on error.

#### 15.337.2.2 free\_fd()

```
virtual cxx::Ref_ptr< File > L4Re::Vfs::Fs::free_fd (
    int fd) [pure virtual], [noexcept]
```

Free the file descriptor *fd*.

#### Parameters

<i>fd</i>	The file descriptor to free.
-----------	------------------------------

#### Returns

A pointer to the file object that was assigned to the fd.

### 15.337.2.3 get\_file()

```
virtual cxx::Ref_ptr< File > L4Re::Vfs::Fs::get_file (
    int fd) [pure virtual], [noexcept]
```

Get the [L4Re::Vfs::File](#) for the file descriptor *fd*.

#### Parameters

<i>fd</i>	The POSIX file descriptor number.
-----------	-----------------------------------

#### Returns

A pointer to the [File](#) object, or 0 if *fd* is not open.

### 15.337.2.4 mount()

```
virtual int L4Re::Vfs::Fs::mount (
    char const * path,
    cxx::Ref_ptr< File > const & dir) [pure virtual], [noexcept]
```

Mount a given file object at the given global path in the VFS.

#### Parameters

<i>path</i>	The global path to mount <i>dir</i> at.
<i>dir</i>	A pointer to the file/directory object that shall be mounted at <i>path</i> .

#### Returns

0 on success, or <0 on error.


References [mount\(\)](#).

Referenced by [mount\(\)](#), and [mount\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 15.337.2.5 set\_fd()

```
virtual cxx::Pair< cxx::Ref_ptr< File >, int > L4Re::Vfs::Fs::set_fd (
    int fd,
    cxx::Ref_ptr< File > const & f = cxx::Ref_ptr<>::Nil) [pure virtual], [noexcept]
```

Set the file object referenced by the file descriptor *fd*.

#### Parameters

<i>fd</i>	The file descriptor to set to <i>f</i> .
<i>f</i>	The file object to assign.

#### Returns

A pair of a pointer to the file object that was previously assigned to *fd* (*first*) and a return value (*second*). *second* contains `−#EBADF` if the passed file descriptor is outside the valid range. *first* contains a Nil pointer in that case. On success, *second* contains 0.

The documentation for this class was generated from the following files:


- l4/l4re\_vfs/vfs.h
- l4/l4re\_vfs/impl/vfs\_impl.h

## 15.338 L4Re::Vfs::Generic\_file Class Reference


The common interface for an open POSIX file.

```
#include <vfs.h>
```

Inheritance diagram for L4Re::Vfs::Generic\_file:



Collaboration diagram for L4Re::Vfs::Generic\_file:



## Public Types

- enum [Ready\\_type](#) : unsigned  
*Type of I/O operation/condition a file can indicate readiness.*

## Public Member Functions

- virtual int [unlock\\_all\\_locks](#) () noexcept=0  
*Unlock all locks on the file.*
- virtual int [fstat](#) (struct stat64 \*buf) const noexcept=0  
*Get status information for the file.*
- virtual int [fchmod](#) (mode\_t) noexcept=0  
*Change POSIX access rights on the file.*
- virtual int [get\\_status\\_flags](#) () const noexcept=0  
*Get file status flags (fcntl F\_GETFL).*
- virtual int [set\\_status\\_flags](#) (long flags) noexcept=0  
*Set file status flags (fcntl F\_SETFL).*
- virtual bool [check\\_ready](#) ([Ready\\_type](#) rt) noexcept=0  
*Check whether the file is ready for an I/O operation/condition.*

### 15.338.1 Detailed Description

The common interface for an open POSIX file.

This interface is common to all kinds of open files, independent of the file type (e.g., directory, regular file etc.). However, in the [L4Re::Vfs](#) the interface [File](#) is used for every real object.

See also

[L4Re::Vfs::File](#) for more information.

Definition at line 52 of file [vfs.h](#).



## 15.338.2 Member Enumeration Documentation

### 15.338.2.1 Ready\_type

```
enum L4Re::Vfs::Generic_file::Ready_type : unsigned
```

Type of I/O operation/condition a file can indicate readiness.

As defined by select() and similar functions.

Definition at line 60 of file [vfs.h](#).

## 15.338.3 Member Function Documentation

### 15.338.3.1 check\_ready()

```
virtual bool L4Re::Vfs::Generic_file::check_ready (
    Ready_type rt) [pure virtual], [noexcept]
```

Check whether the file is ready for an I/O operation/condition.

This method is used by the implementation of select() and similar functions.

#### Parameters

<i>rt</i>	Type of the I/O operation/condition to be ready, as defined by the select() and similar functions (Read, Write, Exception).
-----------	---

#### Return values


<i>true</i>	The file is ready for the given type of I/O operation/condition.
<i>false</i>	The file is not ready for the given type of I/O operation/condition.

Implemented in [L4Re::Vfs::Be\\_file](#).


References [check\\_ready\(\)](#).

Referenced by [check\\_ready\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 15.338.3.2 fchmod()

```
virtual int L4Re::Vfs::Generic_file::fchmod (
    mode_t ) [pure virtual], [noexcept]
```

Change POSIX access rights on the file.


Backend for POSIX chmod and fchmod.

Implemented in [L4Re::Vfs::Be\\_file](#).


References [fchmod\(\)](#).

Referenced by [fchmod\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 15.338.3.3 fstat()

```
virtual int L4Re::Vfs::Generic_file::fstat (  
    struct stat64 * buf) const [pure virtual], [noexcept]
```

Get status information for the file.

This is the backend for POSIX fstat, stat, fstat64 and friends.

#### Parameters

out	<i>buf</i>	This buffer is filled with the status information.
-----	------------	--

#### Returns


0 on success, or <0 on error.

Implemented in [L4Re::Vfs::Be\\_file](#).


References [fstat\(\)](#).

Referenced by [fstat\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



#### 15.338.3.4 `get_status_flags()`

```
virtual int L4Re::Vfs::Generic_file::get_status_flags () const [pure virtual], [noexcept]
```

Get file status flags (fcntl F\_GETFL).

This function is used by the fcntl implementation for the F\_GETFL command.

##### Returns


flags such as O\_RDONLY, O\_WRONLY, O\_RDWR, O\_DIRECT, O\_ASYNC, O\_NOATIME, O\_NONBLOCK, or <0 on error.

Implemented in [L4Re::Vfs::Be\\_file](#).


References [get\\_status\\_flags\(\)](#).

Referenced by [get\\_status\\_flags\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 15.338.3.5 set\_status\_flags()

```
virtual int L4Re::Vfs::Generic_file::set_status_flags (  
    long flags) [pure virtual], [noexcept]
```

Set file status flags (fcntl F\_SETFL).

This function is used by the fcntl implementation for the F\_SETFL command.

#### Parameters

<i>flags</i>	The file status flags to set. This must be a combination of O_RDONLY, O_WRONLY, O_RDWR, O_APPEND, O_ASYNC, O_DIRECT, O_NOATIME, O_NONBLOCK.
--------------	---

#### Note

Creation flags such as O\_CREAT, O\_EXCL, O\_NOCTTY, O\_TRUNC are ignored.

#### Returns


0 on success, or <0 on error.

Implemented in [L4Re::Vfs::Be\\_file](#).


References [set\\_status\\_flags\(\)](#).

Referenced by [set\\_status\\_flags\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 15.338.3.6 unlock\_all\_locks()

```
virtual int L4Re::Vfs::Generic_file::unlock_all_locks () [pure virtual], [noexcept]
```

Unlock all locks on the file.

#### Note

All locks means all locks independent of which file the locks were taken by.

This method is called by the POSIX close implementation to get the POSIX semantics of releasing all locks taken by this application on a close for any fd referencing the real file.

#### Returns


0 on success, or <0 on error.

Implemented in [L4Re::Vfs::Be\\_file](#).


References [unlock\\_all\\_locks\(\)](#).

Referenced by [unlock\\_all\\_locks\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



The documentation for this class was generated from the following file:


- [l4/l4re\\_vfs/vfs.h](#)

## 15.339 L4Re::Vfs::Mman Class Reference


Interface for POSIX memory management.

```
#include <vfs.h>
```

Inheritance diagram for L4Re::Vfs::Mman:



Collaboration diagram for L4Re::Vfs::Mman:



## Public Member Functions

- virtual int **mmap2** (void \*start, size\_t len, int prot, int flags, int fd, off\_t offset, void \*\*ptr) noexcept=0  
*Backend for the mmap2 system call.*
- virtual int **munmap** (void \*start, size\_t len) noexcept=0  
*Backend for the munmap system call.*
- virtual int **mremap** (void \*old, size\_t old\_sz, size\_t new\_sz, int flags, void \*\*new\_addr) noexcept=0  
*Backend for the mremap system call.*
- virtual int **mprotect** (const void \*a, size\_t sz, int prot) noexcept=0  
*Backend for the mprotect system call.*
- virtual int **msync** (void \*addr, size\_t len, int flags) noexcept=0  
*Backend for the msync system call.*
- virtual int **madvise** (void \*addr, size\_t len, int advice) noexcept=0  
*Backend for the madvise system call.*

### 15.339.1 Detailed Description

Interface for POSIX memory management.

#### Note

This interface usually exists as a singleton and as a superclass of [L4Re::Vfs::Ops](#).

An implementation for this interface is in [l4/l4re\\_vfs/impl/vfs\\_impl.h](#) and used by the l4re\_vfs library or by the VFS implementation in ldso.

Definition at line 773 of file [vfs.h](#).

The documentation for this class was generated from the following file:

- l4/l4re\_vfs/vfs.h


## 15.340 L4Re::Vfs::Ops Class Reference

Interface for the POSIX backends of an application.


```
#include <vfs.h>
```



Inheritance diagram for L4Re::Vfs::Ops:



Collaboration diagram for L4Re::Vfs::Ops:



### Additional Inherited Members

### Public Member Functions inherited from [L4Re::Vfs::Mman](#)

- virtual int **mmap2** (void \*start, size\_t len, int prot, int flags, int fd, off\_t offset, void \*\*ptr) noexcept=0  
*Backend for the mmap2 system call.*
- virtual int **munmap** (void \*start, size\_t len) noexcept=0  
*Backend for the munmap system call.*
- virtual int **mremap** (void \*old, size\_t old\_sz, size\_t new\_sz, int flags, void \*\*new\_addr) noexcept=0  
*Backend for the mremap system call.*
- virtual int **mprotect** (const void \*a, size\_t sz, int prot) noexcept=0  
*Backend for the mprotect system call.*
- virtual int **msync** (void \*addr, size\_t len, int flags) noexcept=0  
*Backend for the msync system call.*
- virtual int **madvice** (void \*addr, size\_t len, int advice) noexcept=0  
*Backend for the madvice system call.*

## Public Member Functions inherited from L4Re::Vfs::Fs

- virtual `cx::Ref_ptr< File > get_file` (int fd) noexcept=0  
*Get the L4Re::Vfs::File for the file descriptor fd.*
- virtual `cx::Ref_ptr< File > get_root` () noexcept=0  
*Get the directory object for the application's root directory.*
- virtual `cx::Ref_ptr< File > get_cwd` () noexcept  
*Get the directory object for the application's current working directory.*
- virtual void `set_cwd` (cx::Ref\_ptr< File > const &) noexcept  
*Set the current working directory for the application.*
- virtual int `alloc_fd` (cx::Ref\_ptr< File > const &f=cx::Ref\_ptr<>::Nil) noexcept=0  
*Allocate the next free file descriptor.*
- virtual `cx::Pair< cx::Ref_ptr< File >, int > set_fd` (int fd, cx::Ref\_ptr< File > const &f=cx::Ref\_ptr<>::Nil) noexcept=0  
*Set the file object referenced by the file descriptor fd.*
- virtual `cx::Ref_ptr< File > free_fd` (int fd) noexcept=0  
*Free the file descriptor fd.*
- virtual int `mount` (char const \*path, cx::Ref\_ptr< File > const &dir) noexcept=0  
*Mount a given file object at the given global path in the VFS.*
- int `mount` (char const \*source, char const \*target, char const \*fstype, unsigned long mountflags, void const \*data) noexcept  
*Backend for the POSIX mount call.*

### 15.340.1 Detailed Description

Interface for the POSIX backends of an application.

#### Note

There usually exists a single instance of this interface available via `L4Re::Vfs::vfs_ops` that is used for all kinds of C-Library functions.

Definition at line 1109 of file `vfs.h`.

The documentation for this class was generated from the following file:


- `l4/l4re_vfs/vfs.h`

## 15.341 L4Re::Vfs::Regular\_file Class Reference

Interface for a POSIX file that provides regular file semantics.

```
#include <vfs.h>
```

Inheritance diagram for L4Re::Vfs::Regular\_file:



Collaboration diagram for L4Re::Vfs::Regular\_file:

L4Re::Vfs::Regular_file
<ul style="list-style-type: none"> <li>+ data_space()</li> <li>+ readv()</li> <li>+ writev()</li> <li>+ lseek()</li> <li>+ ftruncate()</li> <li>+ fsync()</li> <li>+ fdatsync()</li> <li>+ get_lock()</li> <li>+ set_lock()</li> </ul>

### Public Member Functions

- virtual [L4::Cap](#)< [L4Re::Dataspace](#) > [data\\_space](#) () noexcept=0  
*Get an [L4Re::Dataspace](#) object for the file.*
- virtual ssize\_t [readv](#) (const struct iovec \*, int iovcnt) noexcept=0  
*Read one or more blocks of data from the file.*
- virtual ssize\_t [writev](#) (const struct iovec \*, int iovcnt) noexcept=0  
*Write one or more blocks of data to the file.*
- virtual off64\_t [lseek](#) (off64\_t, int) noexcept=0  
*Change the file pointer.*
- virtual int [ftruncate](#) (off64\_t pos) noexcept=0  
*Truncate the file at the given position.*
- virtual int [fsync](#) () const noexcept=0  
*Sync the data and meta data to persistent storage.*
- virtual int [fdatsync](#) () const noexcept=0  
*Sync the data to persistent storage.*
- virtual int [get\\_lock](#) (struct flock64 \*lock) noexcept=0  
*Test if the given lock can be placed in the file.*
- virtual int [set\\_lock](#) (struct flock64 \*lock, bool wait) noexcept=0  
*Acquire or release the given lock on the file.*

### 15.341.1 Detailed Description

Interface for a POSIX file that provides regular file semantics.

Real objects always use the combined [L4Re::Vfs::File](#) interface.

Definition at line 287 of file [vfs.h](#).

## 15.341.2 Member Function Documentation

### 15.341.2.1 data\_space()

```
virtual L4::Cap< L4Re::Dataspace > L4Re::Vfs::Regular_file::data_space () [pure virtual],
[noexcept]
```

Get an [L4Re::Dataspace](#) object for the file.

This is used as a backend for POSIX mmap and mmap2 functions.

#### Note

mmap is not possible if the function returns an invalid capability.

#### Returns

A capability to an [L4Re::Dataspace](#) that represents the file contents in an [L4Re](#) way.

Implemented in [L4Re::Vfs::Be\\_file](#).

### 15.341.2.2 fdatsync()

```
virtual int L4Re::Vfs::Regular_file::fdatsync () const [pure virtual], [noexcept]
```

Sync the data to persistent storage.

This is the backend for POSIX fdatsync.

Implemented in [L4Re::Vfs::Be\\_file](#).

References [fdatsync\(\)](#).

Referenced by [fdatsync\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 15.341.2.3 fsync()

```
virtual int L4Re::Vfs::Regular_file::fsync () const [pure virtual], [noexcept]
```

Sync the data and meta data to persistent storage.


This is the backend for POSIX fsync.

Implemented in [L4Re::Vfs::Be\\_file](#).


References [fsync\(\)](#).

Referenced by [fsync\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 15.341.2.4 ftruncate()

```
virtual int L4Re::Vfs::Regular_file::ftruncate (
    off64_t pos) [pure virtual], [noexcept]
```

Truncate the file at the given position.

This function is the backend for truncate and friends.

**Parameters**

<i>pos</i>	The offset at which the file shall be truncated.
------------	--

**Returns**


0 on success, or <0 on error.

Implemented in [L4Re::Vfs::Be\\_file](#).


References [ftruncate\(\)](#).

Referenced by [ftruncate\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:

**15.341.2.5 get\_lock()**

```
virtual int L4Re::Vfs::Regular_file::get_lock (
    struct flock64 * lock) [pure virtual], [noexcept]
```

Test if the given lock can be placed in the file.

This function is used as backend for fcntl F\_GETLK commands.



**Parameters**

<i>lock</i>	The lock that shall be placed on the file. The <i>l_type</i> member will contain <code>F_UNLCK</code> if the lock could be placed.
-------------	--

**Returns**


0 on success, <0 on error.

Implemented in [L4Re::Vfs::Be\\_file](#).

References [get\\_lock\(\)](#).

Referenced by [get\\_lock\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:

**15.341.2.6 lseek()**

```
virtual off64_t L4Re::Vfs::Regular_file::lseek (
    off64_t ,
    int ) [pure virtual], [noexcept]
```

Change the file pointer.

This is the backend for POSIX seek, lseek and friends.

**Returns**


The new file position, or <0 on error.

Implemented in [L4Re::Vfs::Be\\_file](#).


References [lseek\(\)](#).

Referenced by [lseek\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:

**15.341.2.7 readv()**

```
virtual ssize_t L4Re::Vfs::Regular_file::readv (  
    const struct iovec * ,  
    int iovcnt) [pure virtual], [noexcept]
```

Read one or more blocks of data from the file.

This function acts as backend for POSIX read and readv calls and reads data starting from the `f_pos` pointer of that open file. The file pointer is advanced according to the number of bytes read.

**Returns**

The number of bytes read from the file, or <0 on error.

Implemented in [L4Re::Vfs::Be\\_file](#).

References [readv\(\)](#).

Referenced by [readv\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:

**15.341.2.8 set\_lock()**

```
virtual int L4Re::Vfs::Regular_file::set_lock (
    struct flock64 * lock,
    bool wait) [pure virtual], [noexcept]
```

Acquire or release the given lock on the file.

This function is used as backend for `fcntl F_SETLK` and `F_SETLKW` commands.

**Parameters**

<i>lock</i>	The lock that shall be placed on the file.
-------------	--

<i>wait</i>	If true, then block if there is a conflicting lock on the file.
-------------	---

**Returns**


0 on success, <0 on error.

Implemented in [L4Re::Vfs::Be\\_file](#).

References [set\\_lock\(\)](#).

Referenced by [set\\_lock\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:

**15.341.2.9 writev()**

```

virtual ssize_t L4Re::Vfs::Regular_file::writev (
    const struct iovec * ,
    int iovcnt) [pure virtual], [noexcept]
  
```

Write one or more blocks of data to the file.

This function acts as backend for POSIX write and writev calls. The data is written starting at the current file pointer and the file pointer must be advanced according to the number of written bytes.

### Returns

The number of bytes written to the file, or <0 on error.

Implemented in [L4Re::Vfs::Be\\_file](#).


References [writev\(\)](#).

Referenced by [writev\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



The documentation for this class was generated from the following file:


- `l4/l4re_vfs/vfs.h`

## 15.342 L4Re::Vfs::Special\_file Class Reference


Interface for a POSIX file that provides special file semantics.

```
#include <vfs.h>
```

Inheritance diagram for L4Re::Vfs::Special\_file:



Collaboration diagram for L4Re::Vfs::Special\_file:



## Public Member Functions

- virtual int [ioctl](#) (unsigned long cmd, va\_list args) noexcept=0  
*The famous IO control.*

### 15.342.1 Detailed Description

Interface for a POSIX file that provides special file semantics.

Real objects always use the combined [L4Re::Vfs::File](#) interface.

Definition at line [420](#) of file [vfs.h](#).

### 15.342.2 Member Function Documentation

#### 15.342.2.1 ioctl()

```
virtual int L4Re::Vfs::Special_file::ioctl (  
    unsigned long cmd,  
    va_list args) [pure virtual], [noexcept]
```

The famous IO control.

Backend for POSIX generic object invocation ioctl.

#### Parameters

<i>cmd</i>	The ioctl command.
<i>args</i>	The arguments for the ioctl, usually some kind of pointer.

#### Returns

>=0 on success, or <0 on error.

Implemented in [L4Re::Vfs::Be\\_file](#).

The documentation for this class was generated from the following file:


- [l4/l4re\\_vfs/vfs.h](#)

## 15.343 L4Re::Video::Color\_component Class Reference

A color component.

```
#include <colors>
```

Collaboration diagram for L4Re::Video::Color\_component:



### Public Member Functions

- **Color\_component ()**  
*Constructor.*
- **Color\_component** (unsigned char bits, unsigned char shift)  
*Constructor.*
- unsigned char **size** () const  
*Return the number of bits used by the component.*
- unsigned char **shift** () const  
*Return the position of the component in the pixel.*
- bool **operator==** (**Color\_component** const &o) const  
*Compare for equality.*
- int **get** (unsigned long v) const  
*Get component from value (normalized to 16bits).*
- long unsigned **set** (int v) const  
*Transform 16bit normalized value to the component in the color space.*
- template<typename OUT>  
void **dump** (OUT &s) const  
*Dump information on the view information to a stream.*



### 15.343.1 Detailed Description

A color component.

Definition at line 21 of file [colors](#).

### 15.343.2 Constructor & Destructor Documentation

#### 15.343.2.1 Color\_component()

```
L4Re::Video::Color_component::Color_component (
    unsigned char bits,
    unsigned char shift) [inline]
```

Constructor.


#### Parameters

<i>bits</i>	Number of bits used by the component
<i>shift</i>	Position in bits of the component in the pixel

Definition at line 36 of file [colors](#).

References [shift\(\)](#).

Here is the call graph for this function:



### 15.343.3 Member Function Documentation

#### 15.343.3.1 dump()

```
template<typename OUT>
void L4Re::Video::Color_component::dump (
    OUT & s) const [inline]
```

Dump information on the view information to a stream.


**Parameters**

s	Stream
---	--------

Definition at line 81 of file [colors](#).

References [shift\(\)](#), and [size\(\)](#).

Here is the call graph for this function:

**15.343.3.2 get()**

```
int L4Re::Video::Color_component::get (
    unsigned long v) const [inline]
```

Get component from value (normalized to 16bits).

**Parameters**

v	Value
---	-------

**Returns**

Converted value

Definition at line 63 of file [colors](#).

**15.343.3.3 operator==()**

```
bool L4Re::Video::Color_component::operator== (
    Color_component const & o) const [inline]
```

Compare for equality.

**Returns**

True if the same components are described, false if not.

Definition at line 55 of file [colors](#).

References [Color\\_component\(\)](#).

Here is the call graph for this function:

**15.343.3.4 set()**

```
long unsigned L4Re::Video::Color_component::set (
    int v) const [inline]
```

Transform 16bit normalized value to the component in the color space.

**Parameters**

<code>v</code>	Value return Converted value.
----------------	-------------------------------

Definition at line 73 of file [colors](#).

**15.343.3.5 shift()**

```
unsigned char L4Re::Video::Color_component::shift () const [inline]
```

Return the position of the component in the pixel.


**Returns**

Position in bits of the component in the pixel

Definition at line 49 of file [colors](#).

Referenced by [Color\\_component\(\)](#), and [dump\(\)](#).

Here is the caller graph for this function:



#### 15.343.3.6 `size()`

```
unsigned char L4Re::Video::Color_component::size () const [inline]
```

Return the number of bits used by the component.


##### Returns

Number of bits used by the component

Definition at line 43 of file [colors](#).

Referenced by [dump\(\)](#).

Here is the caller graph for this function:



The documentation for this class was generated from the following file:


- `l4/re/video/colors`

## 15.344 L4Re::Video::Goos Class Reference


Class that abstracts framebuffers.

```
#include <goos>
```

Inheritance diagram for L4Re::Video::Goos:



Collaboration diagram for L4Re::Video::Goos:



## Data Structures

- struct [Info](#)  
Information structure of a [Goos](#).

## Public Types

- enum [Flags](#) { [F\\_auto\\_refresh](#) = 0x01 , [F\\_pointer](#) = 0x02 , [F\\_dynamic\\_views](#) = 0x04 , [F\\_dynamic\\_buffers](#) = 0x08 }

*Flags for a Goos.*

## Public Member Functions

- [l4\\_ret\\_t info](#) ([Info](#) \*info)  
*Return the [Goos](#) information of the [Goos](#).*
- [l4\\_ret\\_t get\\_static\\_buffer](#) (unsigned idx, [L4::lpc::Out](#)< [L4::Cap](#)< [L4Re::Dataspace](#) > > rbuf)  
*Return a static buffer of a [Goos](#).*
- [l4\\_ret\\_t create\\_buffer](#) (unsigned long size, [L4::lpc::Out](#)< [L4::Cap](#)< [L4Re::Dataspace](#) > > rbuf)  
*Create a buffer.*
- [l4\\_ret\\_t delete\\_buffer](#) (unsigned idx)  
*Delete a buffer.*
- [l4\\_ret\\_t create\\_view](#) ([View](#) \*view, [l4\\_utcb\\_t](#) \*utcb=[l4\\_utcb](#)()) const noexcept  
*Create a view.*
- [l4\\_ret\\_t delete\\_view](#) ([View](#) const &v, [l4\\_utcb\\_t](#) \*utcb=[l4\\_utcb](#)()) const noexcept  
*Delete a view.*
- [View view](#) (unsigned index) const noexcept  
*Return a view.*
- [l4\\_ret\\_t refresh](#) (int x, int y, int w, int h)  
*Trigger refreshing of the given area on the virtual screen.*

## Public Member Functions inherited from [L4::Kobject](#)

- [l4\\_msgtag\\_t dec\\_refcnt](#) ([l4\\_mword\\_t](#) diff, [l4\\_utcb\\_t](#) \*utcb=[l4\\_utcb](#)())  
*Decrement the in kernel reference counter for the object.*

## Additional Inherited Members

## Protected Types inherited from

[L4::Kobject\\_t](#)< [Goos](#), [L4::Kobject](#), [L4RE\\_PROTO\\_GOOS](#) >

- typedef [Goos](#) **Class**  
*The target interface type (inheriting from [Kobject\\_t](#)).*
- typedef [Typeid::Iface](#)< [PROTO](#), [Goos](#) > **\_\_Iface**  
*The interface description for the derived class.*
- typedef [Typeid::Merge\\_list](#)< [Typeid::Iface\\_list](#)< **\_\_Iface** >, typename [L4::Kobject::\\_\\_Iface\\_list](#) > **\_\_Iface\_list**  
*The list of all RPC interfaces provided directly or through inheritance.*

## Protected Member Functions inherited from

[L4::Kobject\\_t](#)< [Goos](#), [L4::Kobject](#), [L4RE\\_PROTO\\_GOOS](#) >

- [L4::Cap](#)< [Class](#) > **c** () const noexcept  
*Get the capability to ourselves.*

## Protected Member Functions inherited from [L4::Kobject](#)

- [l4\\_cap\\_idx\\_t cap](#) () const noexcept  
*Return capability selector.*

## Static Protected Member Functions inherited from [L4::Kobject\\_t](#)< [Goos](#), [L4::Kobject](#), [L4RE\\_PROTO\\_GOOS](#) >

- static void `__check_protocols__()` noexcept  
*Helper to check for protocol conflicts.*

### 15.344.1 Detailed Description

[Class](#) that abstracts framebuffer.

A framebuffer is the pixel data that is displayed on a screen and a [Goos](#) object lets the user manipulate that data. A [Goos](#) makes use of two kinds of objects:

- Buffers in the form of [L4Re::Dataspace](#) objects. These hold the bytes for the pixel data.
- [L4Re::Video::View](#) objects.

Both can either be static, that is their number and configuration is fixed and determined by the framebuffer, or they can be dynamic, with the user allocating them.

Definition at line [223](#) of file [goos](#).

### 15.344.2 Member Enumeration Documentation

#### 15.344.2.1 Flags

```
enum L4Re::Video::Goos::Flags
```

[Flags](#) for a [Goos](#).

#### Enumerator

<code>F_auto_refresh</code>	The graphics display is automatically refreshed.
<code>F_pointer</code>	We have a mouse pointer.
<code>F_dynamic_views</code>	Supports dynamically allocated views.
<code>F_dynamic_buffers</code>	Supports dynamically allocated buffers.

Definition at line [228](#) of file [goos](#).



### 15.344.3 Member Function Documentation

#### 15.344.3.1 create\_buffer()

```
l4_ret_t L4Re::Video::Goos::create_buffer (
    unsigned long size,
    L4::Ipc::Out< L4::Cap< L4Re::Dataspace > > rbuf)
```

Create a buffer.

##### Parameters

<i>size</i>	Size of buffer in bytes.
<i>rbuf</i>	Capability slot to point the buffer dataspace to.

##### Return values

$\geq 0$	Success, the value returned is the buffer index.
$< 0$	Error

Referenced by [get\\_static\\_buffer\(\)](#).

Here is the caller graph for this function:



#### 15.344.3.2 create\_view()

```
l4_ret_t L4Re::Video::Goos::create_view (
    View * view,
    l4_utcb_t * utcb = l4_utcb()) const [inline], [noexcept]
```

Create a view.

##### Parameters

out	<i>view</i>	A view object.
	<i>utcb</i>	UTCB of the caller. This is a default parameter.

##### Return values


$\geq 0$	Success, the value returned is the view index.
$< 0$	Error

Definition at line 312 of file [goos](#).


References [L4::Kobject\\_t< Goos, L4::Kobject, L4RE\\_PROTO\\_GOOS >::c\(\)](#), [L4::Kobject::cap\(\)](#), and [view\(\)](#).

Referenced by [delete\\_buffer\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 15.344.3.3 delete\_buffer()

```
l4_ret_t L4Re::Video::Goos::delete_buffer (
    unsigned idx)
```

Delete a buffer.

#### Parameters

<i>idx</i>	<a href="#">Buffer</a> to delete.
------------	-----------------------------------


**Return values**

0	Success
<0	Error


References [create\\_view\(\)](#), and [delete\\_buffer\(\)](#).

Referenced by [delete\\_buffer\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:

**15.344.3.4 delete\_view()**

```

l4_ret_t L4Re::Video::Goos::delete_view (
    View const & v,
    l4_utcb_t * utcb = l4_utcb()) const [inline], [noexcept]

```

Delete a view.

**Parameters**

<i>v</i>	The view object to delete.
<i>utcb</i>	UTCB of the caller. This is a default parameter.

**Return values**

0	Success
<0	Error

Definition at line 332 of file [goos](#).

References [L4::Kobject\\_t< Goos, L4::Kobject, L4RE\\_PROTO\\_GOOS >::c\(\)](#).

Here is the call graph for this function:

**15.344.3.5 get\_static\_buffer()**

```

l4_ret_t L4Re::Video::Goos::get_static_buffer (
    unsigned idx,
    L4::Ipc::Out< L4::Cap< L4Re::Dataspace > > rbuf)
  
```

Return a static buffer of a [Goos](#).

**Parameters**

<i>idx</i>	Index of the static buffer.
<i>rbuf</i>	Capability slot to point the buffer dataspace to.


**Return values**

0	Success
<0	Error

References [create\\_buffer\(\)](#).

Referenced by [info\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 15.344.3.6 info()

```
l4_ret_t L4Re::Video::Goos::info (
    Info * info)
```

Return the [Goos](#) information of the [Goos](#).

#### Parameters

out	info	<a href="#">Goos</a> information structure pointer.
-----	------	---


#### Return values

0	Success
<0	Error


References [get\\_static\\_buffer\(\)](#), and [info\(\)](#).

Referenced by [info\(\)](#), and [refresh\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 15.344.3.7 view()

```
View L4Re::Video::Goos::view (
    unsigned index) const [inline], [noexcept]
```

Return a view.

#### Parameters

<i>index</i>	Index of the view to return.
--------------	------------------------------

#### Returns

The view.

Definition at line 363 of file `goos`.


References `L4::Kobject::cap()`.

Referenced by `create_view()`.

Here is the call graph for this function:



Here is the caller graph for this function:



The documentation for this class was generated from the following file:


- `I4/re/video/goos`

## 15.345 L4Re::Video::Goos::Info Struct Reference

Information structure of a [Goos](#).

```
#include <goos>
```

Collaboration diagram for L4Re::Video::Goos::Info:



### Public Member Functions

- bool **auto\_refresh** () const  
*Return whether this [Goos](#) does auto refreshing or the view refresh functions must be used to make changes visible.*
- bool **has\_pointer** () const  
*Return whether a pointer is used by the provider of the [Goos](#).*
- bool **has\_dynamic\_views** () const  
*Return whether dynamic view are supported.*
- bool **has\_dynamic\_buffers** () const  
*Return whether dynamic buffers are supported.*



**Data Fields**

- unsigned long **width**  
*Width.*
- unsigned long **height**  
*Height.*
- unsigned **flags**  
*Flags, see [Flags](#).*
- unsigned **num\_static\_views**  
*Number of static view.*
- unsigned **num\_static\_buffers**  
*Number of static buffers.*
- [Pixel\\_info](#) **pixel\_info**  
*Pixel information.*

**15.345.1 Detailed Description**

Information structure of a [Goos](#).

Definition at line 237 of file [goos](#).

The documentation for this struct was generated from the following file:

- l4/re/video/goos

**15.346 L4Re::Video::Pixel\_info Class Reference**

Pixel information.

```
#include <colors>
```

Collaboration diagram for L4Re::Video::Pixel\_info:

L4Re::Video::Pixel_info
<ul style="list-style-type: none"> <li>+ r()</li> <li>+ g()</li> <li>+ b()</li> <li>+ a()</li> <li>+ padding()</li> <li>+ bytes_per_pixel()</li> <li>+ bits_per_pixel()</li> <li>+ has_alpha()</li> <li>+ r()</li> <li>+ g()</li> <li>and 8 more...</li> </ul>

## Public Member Functions

- [Color\\_component](#) const & [r](#) () const  
*Return the red color compoment of the pixel.*
- [Color\\_component](#) const & [g](#) () const  
*Return the green color compoment of the pixel.*
- [Color\\_component](#) const & [b](#) () const  
*Return the blue color compoment of the pixel.*
- [Color\\_component](#) const & [a](#) () const  
*Return the alpha color compoment of the pixel.*
- [Color\\_component](#) const [padding](#) () const  
*Compute the padding pseudo component.*
- unsigned char [bytes\\_per\\_pixel](#) () const  
*Query size of pixel in bytes.*
- unsigned char [bits\\_per\\_pixel](#) () const  
*Number of bits of the pixel.*
- bool [has\\_alpha](#) () const  
*Return whether the pixel has an alpha channel.*
- void [r](#) ([Color\\_component](#) const &c)  
*Set the red color component of the pixel.*
- void [g](#) ([Color\\_component](#) const &c)  
*Set the green color component of the pixel.*
- void [b](#) ([Color\\_component](#) const &c)  
*Set the blue color component of the pixel.*
- void [a](#) ([Color\\_component](#) const &c)  
*Set the alpha color component of the pixel.*
- void [bytes\\_per\\_pixel](#) (unsigned char bpp)  
*Set the size of the pixel in bytes.*
- **Pixel\_info** ()  
*Constructor.*
- [Pixel\\_info](#) (unsigned char bpp, char [r](#), char [rs](#), char [g](#), char [gs](#), char [b](#), char [bs](#), char [a](#)=0, char [as](#)=0)  
*Constructor.*
- template<typename VBI>  
[Pixel\\_info](#) (VBI const \*vbi)  
*Convenience constructor.*
- bool [operator==](#) ([Pixel\\_info](#) const &o) const  
*Compare for complete equality of the color space.*
- template<typename OUT>  
void [dump](#) (OUT &s) const  
*Dump information on the pixel to a stream.*

### 15.346.1 Detailed Description

Pixel information.

This class wraps the information on a pixel, such as the size and position of each color component in the pixel.

Definition at line 94 of file [colors](#).

## 15.346.2 Constructor & Destructor Documentation

### 15.346.2.1 Pixel\_info() [1/2]

```
L4Re::Video::Pixel_info::Pixel_info (  
    unsigned char bpp,  
    char r,  
    char rs,  
    char g,  
    char gs,  
    char b,  
    char bs,  
    char a = 0,  
    char as = 0) [inline]
```

Constructor.


#### Parameters

<i>bpp</i>	Size of pixel in bytes.
<i>r</i>	Red component size.
<i>rs</i>	Red component shift.
<i>g</i>	Green component size.
<i>gs</i>	Green component shift.
<i>b</i>	Blue component size.
<i>bs</i>	Blue component shift.
<i>a</i>	Alpha component size, defaults to 0.
<i>as</i>	Alpha component shift, defaults to 0.

Definition at line 212 of file [colors](#).

References [a\(\)](#), [b\(\)](#), [g\(\)](#), and [r\(\)](#).

Here is the call graph for this function:



### 15.346.2.2 Pixel\_info() [2/2]

```
template<typename VBI>
L4Re::Video::Pixel_info::Pixel_info (
    VBI const * vbi) [inline], [explicit]
```

Convenience constructor.


#### Parameters

<i>vbi</i>	Suitable information structure. Convenience constructor to create the pixel info from a VESA Framebuffer Info.
------------	--

Definition at line 224 of file [colors](#).

References [bits\\_per\\_pixel\(\)](#).

Here is the call graph for this function:



### 15.346.3 Member Function Documentation

#### 15.346.3.1 a() [1/2]

```
Color_component const & L4Re::Video::Pixel_info::a () const [inline]
```

Return the alpha color compoment of the pixel.


##### Returns

Alpha color component.

Definition at line 123 of file [colors](#).

Referenced by [dump\(\)](#), and [Pixel\\_info\(\)](#).

Here is the caller graph for this function:



#### 15.346.3.2 a() [2/2]

```
void L4Re::Video::Pixel_info::a (
    Color_component const & c) [inline]
```

Set the alpha color component of the pixel.

##### Parameters

<i>c</i>	Alpha color component.
----------	------------------------

Definition at line 187 of file [colors](#).

**15.346.3.3 b()** [1/2]

```
Color_component const & L4Re::Video::Pixel_info::b () const [inline]
```

Return the blue color compoment of the pixel.


**Returns**

Blue color component.

Definition at line 117 of file [colors](#).

Referenced by [dump\(\)](#), and [Pixel\\_info\(\)](#).

Here is the caller graph for this function:

**15.346.3.4 b()** [2/2]

```
void L4Re::Video::Pixel_info::b (
    Color_component const & c) [inline]
```

Set the blue color component of the pixel.

**Parameters**

<i>c</i>	Blue color component.
----------	-----------------------

Definition at line 181 of file [colors](#).

### 15.346.3.5 bits\_per\_pixel()

```
unsigned char L4Re::Video::Pixel_info::bits_per_pixel () const [inline]
```

Number of bits of the pixel.


#### Returns

Number of bits used by the pixel.

Definition at line 156 of file [colors](#).

Referenced by [Pixel\\_info\(\)](#).

Here is the caller graph for this function:



### 15.346.3.6 bytes\_per\_pixel() [1/2]

```
unsigned char L4Re::Video::Pixel_info::bytes_per_pixel () const [inline]
```

Query size of pixel in bytes.

#### Returns

Size of pixel in bytes.

Definition at line 150 of file [colors](#).

Referenced by [dump\(\)](#).

Here is the caller graph for this function:



### 15.346.3.7 bytes\_per\_pixel() [2/2]

```
void L4Re::Video::Pixel_info::bytes_per_pixel (  
    unsigned char bpp) [inline]
```

Set the size of the pixel in bytes.

#### Parameters

<i>bpp</i>	Size of pixel in bytes.
------------	-------------------------

Definition at line 193 of file [colors](#).

### 15.346.3.8 dump()

```
template<typename OUT>  
void L4Re::Video::Pixel_info::dump (  
    OUT & s) const [inline]
```

Dump information on the pixel to a stream.


#### Parameters

<i>s</i>	Stream
----------	--------

Definition at line 246 of file [colors](#).

References [a\(\)](#), [b\(\)](#), [bytes\\_per\\_pixel\(\)](#), [g\(\)](#), and [r\(\)](#).

Here is the call graph for this function:





**15.346.3.9 g()** [1/2]

```
Color_component const & L4Re::Video::Pixel_info::g () const [inline]
```

Return the green color component of the pixel.


**Returns**

Green color component.

Definition at line 111 of file [colors](#).

Referenced by [dump\(\)](#), and [Pixel\\_info\(\)](#).

Here is the caller graph for this function:

**15.346.3.10 g()** [2/2]

```
void L4Re::Video::Pixel_info::g (
    Color_component const & c) [inline]
```

Set the green color component of the pixel.

**Parameters**

<i>c</i>	Green color component.
----------	------------------------

Definition at line 175 of file [colors](#).

**15.346.3.11 has\_alpha()**

```
bool L4Re::Video::Pixel_info::has_alpha () const [inline]
```

Return whether the pixel has an alpha channel.

**Returns**

True if the pixel has an alpha channel, false if not.

Definition at line 163 of file [colors](#).

### 15.346.3.12 operator==( )

```
bool L4Re::Video::Pixel_info::operator== (
    Pixel_info const & o) const [inline]
```

Compare for complete equality of the color space.

#### Parameters

<i>o</i>	A <a href="#">Pixel_info</a> to compare to.
----------	---


#### Returns

true if the both [Pixel\\_info](#)'s are equal, false if not.

Definition at line [236](#) of file [colors](#).

References [Pixel\\_info\(\)](#).

Here is the call graph for this function:



### 15.346.3.13 padding()

```
Color_component const L4Re::Video::Pixel_info::padding () const [inline]
```

Compute the padding pseudo component.

The padding pseudo component represents the tailing bits that are reserved in RGB32 and similar pixel formats.

#### Returns

Padding pseudo component.

Definition at line [131](#) of file [colors](#).

**15.346.3.14** `r()` [1/2]

```
Color_component const & L4Re::Video::Pixel_info::r () const [inline]
```

Return the red color component of the pixel.


**Returns**

Red color component.

Definition at line 105 of file [colors](#).

Referenced by [dump\(\)](#), and [Pixel\\_info\(\)](#).

Here is the caller graph for this function:

**15.346.3.15** `r()` [2/2]

```
void L4Re::Video::Pixel_info::r (
    Color_component const & c) [inline]
```

Set the red color component of the pixel.

**Parameters**

<code>c</code>	Red color component.
----------------	----------------------

Definition at line 169 of file [colors](#).

The documentation for this class was generated from the following file:

- `I4/re/video/colors`

## 15.347 L4Re::Video::View Class Reference

[View](#) of a framebuffer.

```
#include <goos>
```

Collaboration diagram for L4Re::Video::View:

L4Re::Video::View
<ul style="list-style-type: none"> <li>+ info()</li> <li>+ set_info()</li> <li>+ set_viewport()</li> <li>+ stack()</li> <li>+ push_top()</li> <li>+ push_bottom()</li> <li>+ refresh()</li> <li>+ valid()</li> </ul>

### Data Structures

- struct [Info](#)  
*Information structure of a view.*

### Public Types

- enum [Flags](#) {  
[F\\_none](#) = 0x00 , [F\\_set\\_buffer](#) = 0x01 , [F\\_set\\_buffer\\_offset](#) = 0x02 , [F\\_set\\_bytes\\_per\\_line](#) = 0x04 ,  
[F\\_set\\_pixel](#) = 0x08 , [F\\_set\\_position](#) = 0x10 , [F\\_dyn\\_allocated](#) = 0x20 , [F\\_set\\_background](#) = 0x40 ,  
[F\\_set\\_flags](#) = 0x80 , [F\\_fully\\_dynamic](#) }  
*Flags on a view.*
- enum [V\\_flags](#) { [F\\_above](#) = 0x1000 , [F\\_flags\\_mask](#) = 0xff000 }  
*Property flags of a view.*

## Public Member Functions

- `int info (Info *info) const noexcept`  
*Return the view information of the view.*
- `int set_info (Info const &info) const noexcept`  
*Set the information structure for this view.*
- `int set_viewport (int scr_x, int scr_y, int w, int h, unsigned long buf_offset) const noexcept`  
*Set the position of the view in the [Goos](#).*
- `int stack (View const &pivot, bool behind=true) const noexcept`  
*Move this view in the view stack.*
- `int push_top () const noexcept`  
*Make this view the top-most view.*
- `int push_bottom () const noexcept`  
*Push this view the back.*
- `int refresh (int x, int y, int w, int h) const noexcept`  
*Refresh/Redraw the view.*
- `bool valid () const`  
*Return whether this view is valid.*

## 15.347.1 Detailed Description

[View](#) of a framebuffer.

A view is a rectangular subset of a framebuffer managed by a [Goos](#) object. The [Goos](#) orders multiple views in a stack which determines which view is on top in case they overlap. The view's pixel data is provided by a backing buffer, which must belong to the [Goos](#). It can be static or dynamically allocated, depending on the framebuffer.

See also

[L4Re::Video::Goos](#)

Definition at line 39 of file [goos](#).

## 15.347.2 Member Enumeration Documentation

### 15.347.2.1 Flags

enum [L4Re::Video::View::Flags](#)

[Flags](#) on a view.

#### Enumerator

<code>F_none</code>	everything for this view is static (the VESA-FB case)
<code>F_set_buffer</code>	buffer object for this view can be changed
<code>F_set_buffer_offset</code>	buffer offset can be set
<code>F_set_bytes_per_line</code>	bytes per line can be set

F_set_pixel	pixel type can be set
F_set_position	position on screen can be set
F_dyn_allocated	<a href="#">View</a> is dynamically allocated.
F_set_background	Set view as background for session.
F_set_flags	Set view flags (.  See also  <a href="#">V_flags</a> )
F_fully_dynamic	<a href="#">Flags</a> for a fully dynamic view.

Definition at line 59 of file [goos](#).

### 15.347.2.2 V\_flags

```
enum L4Re::Video::View::V_flags
```

Property flags of a view.

Such flags can be set or deleted with the [F\\_set\\_flags](#) operation using the [set\\_info\(\)](#) method.

#### Enumerator

F_above	Flag the view as stay on top.
F_flags_mask	Mask containing all possible property flags.

Definition at line 82 of file [goos](#).

## 15.347.3 Member Function Documentation

### 15.347.3.1 info()

```
int L4Re::Video::View::info (
    Info * info) const [inline], [noexcept]
```

Return the view information of the view.

#### Parameters

out	<i>info</i>	Information structure pointer.
-----	-------------	--------------------------------

#### Return values

0	Success
---	---------

<0	Error
----	-------

Definition at line 367 of file [goos](#).


References [info\(\)](#).

Referenced by [info\(\)](#), and [set\\_info\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 15.347.3.2 refresh()

```

int L4Re::Video::View::refresh (
    int x,
    int y,
    int w,
    int h) const [inline], [noexcept]
  
```

Refresh/Redraw the view.

#### Parameters

<i>x</i>	X position.
<i>y</i>	Y position.
<i>w</i>	Width.
<i>h</i>	Height.

**Return values**

0	Success
<0	Error

Definition at line 379 of file [goos](#).

**15.347.3.3 set\_info()**

```
int L4Re::Video::View::set_info (  
    Info const & info) const [inline], [noexcept]
```

Set the information structure for this view.

**Parameters**

<i>info</i>	Information structure.
-------------	------------------------

**Return values**

0	Success
<0	Error


The function will also set the view port according to the values given in the information structure.

Definition at line 371 of file [goos](#).

References [info\(\)](#).


Referenced by [set\\_viewport\(\)](#).

Here is the call graph for this function:





Here is the caller graph for this function:



#### 15.347.3.4 set\_viewport()

```
int L4Re::Video::View::set_viewport (
    int scr_x,
    int scr_y,
    int w,
    int h,
    unsigned long buf_offset) const [inline], [noexcept]
```

Set the position of the view in the [Goos](#).

##### Parameters

<i>scr_x</i>	X position
<i>scr_y</i>	Y position
<i>w</i>	Width
<i>h</i>	Height
<i>buf_offset</i>	Offset in the buffer in bytes


##### Return values

0	Success
<0	Error

Definition at line [383](#) of file [goos](#).

References [L4Re::Video::View::Info::buffer\\_index](#), [L4Re::Video::View::Info::buffer\\_offset](#), [L4Re::Video::View::Info::bytes\\_per\\_line](#), [F\\_set\\_buffer\\_offset](#), [F\\_set\\_position](#), [L4Re::Video::View::Info::flags](#), [L4Re::Video::View::Info::height](#), [L4Re::Video::View::Info::pixel\\_info](#), [set\\_info\(\)](#), [L4Re::Video::View::Info::view\\_index](#), [L4Re::Video::View::Info::width](#), [L4Re::Video::View::Info::xpos](#), and [L4Re::Video::View::Info::ypos](#).

Here is the call graph for this function:



### 15.347.3.5 stack()

```
int L4Re::Video::View::stack (
    View const & pivot,
    bool behind = true) const [inline], [noexcept]
```

Move this view in the view stack.

#### Parameters

<i>pivot</i>	<a href="#">View</a> to move relative to
<i>behind</i>	When true move the view behind the pivot view, if false move the view before the pivot view.


#### Return values

0	Success
<0	Error

Definition at line 375 of file [goos](#).

Referenced by [push\\_bottom\(\)](#), and [push\\_top\(\)](#).

Here is the caller graph for this function:



The documentation for this class was generated from the following file:


- `l4/re/video/goos`

## 15.348 L4Re::Video::View::Info Struct Reference

Information structure of a view.

```
#include <goos>
```

Collaboration diagram for L4Re::Video::View::Info:



## Public Member Functions

- bool **has\_static\_buffer** () const  
*Return whether the view has a static buffer.*
- bool **has\_static\_buffer\_offset** () const  
*Return whether the static buffer offset is available.*
- bool **has\_set\_buffer** () const  
*Return whether a buffer is set.*
- bool **has\_set\_buffer\_offset** () const  
*Return whether the given buffer offset is valid.*
- bool **has\_set\_bytes\_per\_line** () const  
*Return whether the given bytes-per-line value is valid.*
- bool **has\_set\_pixel** () const  
*Return whether the given pixel information is valid.*
- bool **has\_set\_position** () const  
*Return whether the position information given is valid.*
- template<typename OUT>  
void **dump** (OUT &s) const  
*Dump information on the view information to a stream.*

## Data Fields

- unsigned **flags** = 0  
*Flags, see [Flags](#) and [V\\_flags](#).*
- unsigned **view\_index** = 0  
*Index of the view.*
- unsigned long **xpos** = 0  
*X position in pixels of the view in the [Goos](#).*
- unsigned long **ypos** = 0  
*Y position in pixels of the view in the [Goos](#).*
- unsigned long **width** = 0  
*Width of the view in pixels.*
- unsigned long **height** = 0  
*Height of the view in pixels.*
- unsigned long **buffer\_offset** = 0  
*Offset in the memory buffer in bytes.*
- unsigned long **bytes\_per\_line** = 0  
*Bytes per line.*
- [Pixel\\_info](#) **pixel\_info**  
*Pixel information.*
- unsigned **buffer\_index** = 0  
*Number of the buffer used for this view.*

## 15.348.1 Detailed Description

Information structure of a view.

Definition at line 91 of file [goos](#).

The documentation for this struct was generated from the following file:

- l4/re/video/goos

## 15.349 l4re\_aux\_t Struct Reference

Auxiliary descriptor.

```
#include <l4aux.h>
```

Collaboration diagram for l4re\_aux\_t:

l4re_aux_t
+ binary
+ kip_ds
+ dbg_lvl
+ ldr_flags
+ ldr_base

### Data Fields

- char const \* **binary**  
*Binary name.*
- [l4\\_cap\\_idx\\_t](#) **kip\_ds**  
*Data space of the KIP.*
- [l4\\_umword\\_t](#) **dbg\_lvl**  
*Debug levels for l4re.*
- [l4\\_umword\\_t](#) **ldr\_flags**  
*Flags for l4re, see [l4re\\_aux\\_ldr\\_flags\\_t](#).*
- [l4\\_addr\\_t](#) **ldr\_base**  
*Load offset of executable.*

### 15.349.1 Detailed Description

Auxiliary descriptor.

Definition at line 40 of file [l4aux.h](#).

The documentation for this struct was generated from the following file:


- [l4/re/l4aux.h](#)

## 15.350 l4re\_ds\_stats\_t Struct Reference

Information about the data space.

```
#include <dataspace.h>
```

Collaboration diagram for l4re\_ds\_stats\_t:



### Data Fields

- l4re\_ds\_size\_t **size**  
*size*
- l4re\_ds\_flags\_t **flags**  
*flags*

### 15.350.1 Detailed Description

Information about the data space.

Definition at line 39 of file [dataspace.h](#).

The documentation for this struct was generated from the following file:


- l4/re/c/[dataspace.h](#)

## 15.351 l4re\_elf\_aux\_mword\_t Struct Reference

Auxiliary vector element for a single unsigned data word.

```
#include <elf_aux.h>
```

Collaboration diagram for l4re\_elf\_aux\_mword\_t:



### 15.351.1 Detailed Description

Auxiliary vector element for a single unsigned data word.

Definition at line 118 of file [elf\\_aux.h](#).

The documentation for this struct was generated from the following file:


- [l4re/elf\\_aux.h](#)

## 15.352 l4re\_elf\_aux\_t Struct Reference

Generic header for each auxiliary vector element.

```
#include <elf_aux.h>
```

Collaboration diagram for l4re\_elf\_aux\_t:



### 15.352.1 Detailed Description

Generic header for each auxiliary vector element.

Definition at line 98 of file [elf\\_aux.h](#).

The documentation for this struct was generated from the following file:


- [l4re/elf\\_aux.h](#)

## 15.353 l4re\_elf\_aux\_vma\_t Struct Reference

Auxiliary vector element for a reserved virtual memory area.

```
#include <elf_aux.h>
```

Collaboration diagram for l4re\_elf\_aux\_vma\_t:



### 15.353.1 Detailed Description

Auxiliary vector element for a reserved virtual memory area.

Definition at line 107 of file [elf\\_aux.h](#).

The documentation for this struct was generated from the following file:


- [l4/re/elf\\_aux.h](#)

## 15.354 l4re\_env\_cap\_entry\_t Struct Reference

Entry in the [L4Re](#) environment array for the named initial objects.

```
#include <env.h>
```

Collaboration diagram for l4re\_env\_cap\_entry\_t:





## Public Member Functions

- [l4re\\_env\\_cap\\_entry\\_t \(\)](#) [L4\\_NOTHROW](#)  
*Create an invalid entry.*
- [l4re\\_env\\_cap\\_entry\\_t](#) (char const \*n, [l4\\_cap\\_idx\\_t](#) c, [l4\\_umword\\_t](#) f=0) [L4\\_NOTHROW](#)  
*Create an entry with the name n, capability c, and flags f.*

## Data Fields

- [l4\\_cap\\_idx\\_t](#) cap  
*The capability selector for the object.*
- [l4\\_umword\\_t](#) flags  
*Flags for the object.*
- char **name** [16]  
*The name of the object.*

## 15.354.1 Detailed Description

Entry in the [L4Re](#) environment array for the named initial objects.

Definition at line 39 of file [env.h](#).

## 15.354.2 Constructor & Destructor Documentation

### 15.354.2.1 l4re\_env\_cap\_entry\_t()

```
l4re_env_cap_entry_t::l4re_env_cap_entry_t (
    char const * n,
    l4_cap_idx_t c,
    l4_umword_t f = 0) [inline]
```

Create an entry with the name *n*, capability *c*, and flags *f*.

### Parameters

<i>n</i>	is the name of the initial object.
<i>c</i>	is the capability selector that refers the initial object.
<i>f</i>	are the additional flags for the object.

Definition at line 70 of file [env.h](#).

References [cap](#), [flags](#), [L4\\_NOTHROW](#), and [name](#).

### 15.354.3 Field Documentation

#### 15.354.3.1 flags

`l4_umword_t l4re_env_cap_entry_t::flags`

Flags for the object.

##### Note

Currently unused, except as an end marker for the entry list.

Definition at line 50 of file [env.h](#).

Referenced by [l4re\\_env\\_cap\\_entry\\_t\(\)](#), [l4re\\_env\\_cap\\_entry\\_t\(\)](#), and [l4re\\_env\\_get\\_cap\\_l\(\)](#).

The documentation for this struct was generated from the following file:


- [l4/re/env.h](#)

### 15.355 l4re\_env\_t Struct Reference

Initial environment data structure.

```
#include <env.h>
```

Collaboration diagram for l4re\_env\_t:



## Data Fields

- [l4\\_cap\\_idx\\_t](#) **parent**  
*Parent object-capability.*
- [l4\\_cap\\_idx\\_t](#) **rm**  
*Region map object-capability.*
- [l4\\_cap\\_idx\\_t](#) **mem\_alloc**  
*Memory allocator object-capability.*
- [l4\\_cap\\_idx\\_t](#) **log**  
*Logging object-capability.*
- [l4\\_cap\\_idx\\_t](#) **main\_thread**  
*Object-capability of the first user thread.*
- [l4\\_cap\\_idx\\_t](#) **factory**

*Object-capability of the factory available to the task.*

- [l4\\_cap\\_idx\\_t scheduler](#)

*Object capability for the scheduler set to use.*

- [l4\\_cap\\_idx\\_t itas](#)

*ITAS services object-capability.*

- [l4\\_cap\\_idx\\_t dbg\\_events](#)

*Object-capability of the debug events service.*

- [l4\\_cap\\_idx\\_t first\\_free\\_cap](#)

*First capability index available to the application.*

- [l4\\_fpage\\_t utcb\\_area](#)

*UTCB area of the task.*

- [l4\\_addr\\_t first\\_free\\_utcb](#)

*First UTCB within the UTCB area available to the application.*

- [l4re\\_env\\_cap\\_entry\\_t \\* caps](#)

*Pointer to the first entry in the initial objects array which contains [l4re\\_env\\_cap\\_entry\\_t](#) elements.*

### 15.355.1 Detailed Description

Initial environment data structure.

See also

[Initial environment](#)

Definition at line 98 of file [env.h](#).

### 15.355.2 Field Documentation

#### 15.355.2.1 caps

[l4re\\_env\\_cap\\_entry\\_t\\*](#) [l4re\\_env\\_t::caps](#)

Pointer to the first entry in the initial objects array which contains [l4re\\_env\\_cap\\_entry\\_t](#) elements.

The array is terminated by an invalid entry with a `flags` value of `~0u1`.

Definition at line 117 of file [env.h](#).

The documentation for this struct was generated from the following file:


- [l4/re/env.h](#)

## 15.356 l4re\_event\_t Struct Reference

Event structure used in buffer.

```
#include <event.h>
```

Collaboration diagram for l4re\_event\_t:



### Data Fields

- long long **time**  
*Time stamp of the event.*
- unsigned short **type**  
*Type of the event.*
- unsigned short **code**  
*Code of the event.*
- int **value**  
*Value of the event.*
- [l4\\_umword\\_t](#) **stream\_id**  
*Stream ID.*

### 15.356.1 Detailed Description

Event structure used in buffer.

Definition at line 30 of file [event.h](#).

The documentation for this struct was generated from the following file:

- [l4/re/c/event.h](#)

## 15.357 l4re\_video\_color\_component\_t Struct Reference

Color component structure.

```
#include <colors.h>
```

Collaboration diagram for l4re\_video\_color\_component\_t:

l4re_video_color_component_t	
+	size
+	shift

### Data Fields

- unsigned char **size**  
*Size in bits.*
- unsigned char **shift**  
*offset in pixel*

### 15.357.1 Detailed Description

Color component structure.

Definition at line 20 of file [colors.h](#).

The documentation for this struct was generated from the following file:


- [l4re/c/video/colors.h](#)

## 15.358 l4re\_video\_goos\_info\_t Struct Reference

Goos information structure.

```
#include <goos.h>
```

Collaboration diagram for l4re\_video\_goos\_info\_t:



## Data Fields

- unsigned long **width**  
*Width of the goos.*
- unsigned long **height**  
*Height of the goos.*
- unsigned **flags**  
*Flags of the framebuffer, see [l4re\\_video\\_goos\\_info\\_flags\\_t](#).*
- unsigned **num\_static\_views**  
*Number of static views.*
- unsigned **num\_static\_buffers**

*Number of static buffers.*

- [l4re\\_video\\_pixel\\_info\\_t](#) **pixel\_info**

*Pixel layout of the goos.*

### 15.358.1 Detailed Description

Goos information structure.

Definition at line 41 of file [goos.h](#).

The documentation for this struct was generated from the following file:


- [l4re/c/video/goos.h](#)

## 15.359 l4re\_video\_pixel\_info\_t Struct Reference

Pixel\_info structure.

```
#include <colors.h>
```

Collaboration diagram for `l4re_video_pixel_info_t`:





## Data Fields

- [l4re\\_video\\_color\\_component\\_t a](#)  
*Colors.*
- unsigned char **bytes\_per\_pixel**  
*Bytes per pixel.*

## 15.359.1 Detailed Description

Pixel\_info structure.

Definition at line 30 of file [colors.h](#).

The documentation for this struct was generated from the following file:


- [l4re/c/video/colors.h](#)

## 15.360 l4re\_video\_view\_info\_t Struct Reference

View information structure.

```
#include <view.h>
```

Collaboration diagram for `l4re_video_view_info_t`:



## Data Fields

- unsigned **flags**  
*Flags.*
- unsigned **view\_index**  
*Number of view in the goos.*
- unsigned long **height**  
*Position in goos and size of view.*
- unsigned long **buffer\_offset**  
*Memory offset in goos buffer.*

- unsigned long **bytes\_per\_line**  
*Size of line in view.*
- [l4re\\_video\\_pixel\\_info\\_t](#) **pixel\_info**  
*Pixel info.*
- unsigned **buffer\_index**  
*Number of buffer of goos.*

### 15.360.1 Detailed Description

View information structure.

Definition at line 49 of file [view.h](#).

The documentation for this struct was generated from the following file:


- [l4re/c/video/view.h](#)

## 15.361 l4re\_video\_view\_t Struct Reference

C representation of a goos view.

```
#include <view.h>
```

Collaboration diagram for l4re\_video\_view\_t:



### 15.361.1 Detailed Description

C representation of a goos view.

A view is a visible rectangle that provides a view to the contents of a buffer (frame buffer) memory object and is placed on a real screen.

Definition at line 68 of file [view.h](#).

The documentation for this struct was generated from the following file:

- [l4re/c/video/view.h](#)

## 15.362 l4shmc\_ringbuf\_head\_t Struct Reference

Head field of a ring buffer.

```
#include <ringbuf.h>
```

Collaboration diagram for l4shmc\_ringbuf\_head\_t:

l4shmc_ringbuf_head_t
<ul style="list-style-type: none"><li>+ next_read</li><li>+ next_write</li><li>+ bytes_filled</li><li>+ sender_waits</li><li>+ data</li></ul>

### Data Fields

- unsigned **next\_read**  
*offset to next read packet*
- unsigned **next\_write**  
*offset to next write packet*
- unsigned **bytes\_filled**  
*bytes filled in buffer*
- unsigned **sender\_waits**  
*sender waiting?*
- char **data** []  
*tail pointer -> data*

### 15.362.1 Detailed Description

Head field of a ring buffer.

Definition at line 59 of file [ringbuf.h](#).

The documentation for this struct was generated from the following file:


- [l4/shmc/ringbuf.h](#)

## 15.363 l4shmc\_ringbuf\_t Struct Reference

Ring buffer.

```
#include <ringbuf.h>
```

Collaboration diagram for l4shmc\_ringbuf\_t:



### Data Fields

- l4shmc\_area\_t \* **\_area**  
*L4SHM area this buffer is located in.*
- l4\_cap\_idx\_t **\_owner**  
*owner (attached to send/recv signal)*
- l4shmc\_chunk\_t **\_chunk**  
*chunk descriptor*
- unsigned **\_size**

- chunk size // XXX do we need this?*
- `char * _chunkname`  
*name of the ring buffer chunk*
- `char * _signame`  
*base name of the ring buffer signals*
- `l4shmc_ringbuf_head_t * _addr`  
*pointer to ring buffer head*
- `l4shmc_signal_t _signal_full`  
*"full" signal - triggered when data is produced*
- `l4shmc_signal_t _signal_empty`  
*"empty" signal - triggered when data is consumed*

### 15.363.1 Detailed Description

Ring buffer.

Definition at line 85 of file [ringbuf.h](#).

The documentation for this struct was generated from the following file:

- [l4/shmc/ringbuf.h](#)

## 15.364 l4util\_l4mod\_info Struct Reference

Base module structure.

```
#include <l4mod.h>
```

Collaboration diagram for l4util\_l4mod\_info:

l4util_l4mod_info
+ flags
+ cmdline
+ mods_addr
+ mods_count
+ vbe_ctrl_info
+ vbe_mode_info

## Data Fields

- [l4\\_uint64\\_t](#) **flags**  
*Flags.*
- [l4\\_uint64\\_t](#) **cmdline**  
*Pointer to kernel command line.*
- [l4\\_uint64\\_t](#) **mods\_addr**  
*Module list.*
- [l4\\_uint32\\_t](#) **mods\_count**  
*Number of modules.*
- [l4\\_uint64\\_t](#) **vbe\_ctrl\_info**  
*VESA video info, valid if one of vbe\_ctrl\_info or vbe\_mode\_info is not zero.*
- [l4\\_uint64\\_t](#) **vbe\_mode\_info**  
*VESA video mode info.*

## 15.364.1 Detailed Description

Base module structure.

Definition at line 36 of file [l4mod.h](#).

## 15.364.2 Field Documentation

### 15.364.2.1 vbe\_ctrl\_info

[l4\\_uint64\\_t](#) l4util\_l4mod\_info::vbe\_ctrl\_info

VESA video info, valid if one of vbe\_ctrl\_info or vbe\_mode\_info is not zero.

VESA video controller info

Definition at line 48 of file [l4mod.h](#).

The documentation for this struct was generated from the following file:

- [l4/util/l4mod.h](#)

## 15.365 l4util\_l4mod\_mod Struct Reference

A single module.

```
#include <l4mod.h>
```

Collaboration diagram for l4util\_l4mod\_mod:

l4util_l4mod_mod
+ flags
+ mod_start
+ mod_end
+ cmdline

### Data Fields

- [l4\\_uint64\\_t flags](#)  
*Module flags ([l4util\\_l4mod\\_mod\\_info\\_flag](#)).*
- [l4\\_uint64\\_t mod\\_start](#)  
*Starting address of module in memory.*
- [l4\\_uint64\\_t mod\\_end](#)  
*End address of module in memory.*
- [l4\\_uint64\\_t cmdline](#)  
*Module command line.*

### 15.365.1 Detailed Description

A single module.

Definition at line 27 of file [l4mod.h](#).

The documentation for this struct was generated from the following file:

- [l4/util/l4mod.h](#)



## 15.366 l4util\_mb\_addr\_range\_t Struct Reference

INT-15, AX=E820 style "AddressRangeDescriptor" ...with a "size" parameter on the front which is the structure size - 4, pointing to the next one, up until the full buffer length of the memory map has been reached.

```
#include <mb_info.h>
```

Collaboration diagram for l4util\_mb\_addr\_range\_t:

l4util_mb_addr_range_t	
+	struct_size
+	addr
+	size
+	type

### Data Fields

- [l4\\_uint32\\_t](#) **struct\_size**  
*Size of structure.*
- [l4\\_uint64\\_t](#) **addr**  
*Start address.*
- [l4\\_uint64\\_t](#) **size**  
*Size of memory range.*
- [l4\\_uint32\\_t](#) **type**  
*type of memory range*

### 15.366.1 Detailed Description

INT-15, AX=E820 style "AddressRangeDescriptor" ...with a "size" parameter on the front which is the structure size - 4, pointing to the next one, up until the full buffer length of the memory map has been reached.

Definition at line 48 of file [mb\\_info.h](#).

The documentation for this struct was generated from the following file:


- [l4/util/mb\\_info.h](#)

## 15.367 l4util\_mb\_apm\_t Struct Reference

APM BIOS info.

```
#include <mb_info.h>
```

Collaboration diagram for l4util\_mb\_apm\_t:



### 15.367.1 Detailed Description

APM BIOS info.

Definition at line 90 of file [mb\\_info.h](#).

The documentation for this struct was generated from the following file:


- [l4/util/mb\\_info.h](#)

## 15.368 l4util\_mb\_drive\_t Struct Reference

Drive Info structure.

```
#include <mb_info.h>
```

Collaboration diagram for l4util\_mb\_drive\_t:



### Data Fields

- [l4\\_uint8\\_t](#) **drive\_number**  
< The size of this structure.
- [l4\\_uint8\\_t](#) **drive\_mode**  
< The BIOS drive number.
- [l4\\_uint16\\_t](#) **drive\_cylinders**  
< The access mode (see below).
- [l4\\_uint8\\_t](#) **drive\_heads**  
< number of cylinders
- [l4\\_uint8\\_t](#) **drive\_sectors**  
< number of heads
- [l4\\_uint16\\_t](#) **drive\_ports** [0]  
< number of sectors per track

### 15.368.1 Detailed Description

Drive Info structure.

Definition at line 73 of file [mb\\_info.h](#).

The documentation for this struct was generated from the following file:

- [l4/util/mb\\_info.h](#)

## 15.369 l4util\_mb\_info\_t Struct Reference

MultiBoot Info description.

```
#include <mb_info.h>
```

Collaboration diagram for l4util\_mb\_info\_t:

l4util_mb_info_t
+ flags
+ mem_lower
+ mem_upper
+ boot_device
+ cmdline
+ mods_count
+ mods_addr
+ tabsize
+ num
+ mmap_length
and 12 more...

## Data Fields

- [l4\\_uint32\\_t flags](#)  
*MultiBoot info version number.*
- [l4\\_uint32\\_t mem\\_lower](#)  
*available memory below 1MB*
- [l4\\_uint32\\_t mem\\_upper](#)  
*available memory starting from 1MB [KB]*
- [l4\\_uint32\\_t boot\\_device](#)  
*"root" partition*
- [l4\\_uint32\\_t cmdline](#)  
*Kernel command line.*
- [l4\\_uint32\\_t mods\\_count](#)  
*number of modules*
- [l4\\_uint32\\_t mods\\_addr](#)  
*module list*
- [l4\\_uint32\\_t mmap\\_length](#)  
*size of memory mapping buffer*
- [l4\\_uint32\\_t mmap\\_addr](#)  
*address of memory mapping buffer*
- [l4\\_uint32\\_t drives\\_length](#)  
*size of drive info buffer*
- [l4\\_uint32\\_t drives\\_addr](#)  
*address of driver info buffer*
- [l4\\_uint32\\_t config\\_table](#)  
*ROM configuration table.*
- [l4\\_uint32\\_t boot\\_loader\\_name](#)  
*Boot Loader Name.*
- [l4\\_uint32\\_t apm\\_table](#)  
*APM table.*
- [l4\\_uint32\\_t vbe\\_ctrl\\_info](#)  
*VESA video controller info.*
- [l4\\_uint32\\_t vbe\\_mode\\_info](#)  
*VESA video mode info.*
- [l4\\_uint16\\_t vbe\\_mode](#)  
*VESA video mode number.*
- [l4\\_uint16\\_t vbe\\_interface\\_seg](#)  
*VESA segment of prot BIOS interface.*
- [l4\\_uint16\\_t vbe\\_interface\\_off](#)  
*VESA offset of prot BIOS interface.*
- [l4\\_uint16\\_t vbe\\_interface\\_len](#)  
*VESA lenght of prot BIOS interface.*

### 15.369.1 Detailed Description

MultiBoot Info description.

This is the struct passed to the boot image. This is done by placing its address in the EAX register.

Definition at line 247 of file [mb\\_info.h](#).

The documentation for this struct was generated from the following file:


- [l4/util/mb\\_info.h](#)

## 15.370 l4util\_mb\_mod\_t Struct Reference

The structure type "mod\_list" is used by the [multiboot\\_info](#) structure.

```
#include <mb_info.h>
```

Collaboration diagram for l4util\_mb\_mod\_t:



### Data Fields

- [l4\\_uint32\\_t](#) **mod\_start**  
*Starting address of module in memory.*
- [l4\\_uint32\\_t](#) **mod\_end**  
*End address of module in memory.*
- [l4\\_uint32\\_t](#) **cmdline**  
*Module command line.*
- [l4\\_uint32\\_t](#) **pad**  
*padding to take it to 16 bytes*

### 15.370.1 Detailed Description

The structure type "mod\_list" is used by the [multiboot\\_info](#) structure.

Definition at line 33 of file [mb\\_info.h](#).

The documentation for this struct was generated from the following file:


- [l4/util/mb\\_info.h](#)

## 15.371 l4util\_mb\_vbe\_ctrl\_t Struct Reference

VBE controller information.

```
#include <mb_info.h>
```

Collaboration diagram for l4util\_mb\_vbe\_ctrl\_t:



### 15.371.1 Detailed Description

VBE controller information.

Definition at line 106 of file [mb\\_info.h](#).

The documentation for this struct was generated from the following file:

- l4/util/[mb\\_info.h](#)

## 15.372 l4util\_mb\_vbe\_mode\_t Struct Reference

VBE mode information.

```
#include <mb_info.h>
```

Collaboration diagram for l4util\_mb\_vbe\_mode\_t:

l4util_mb_vbe_mode_t
+ mode_attributes
+ win_a_attributes
+ win_b_attributes
+ win_granularity
+ win_size
+ win_a_segment
+ win_b_segment
+ win_func
+ bytes_per_scanline
+ x_resolution
+ y_resolution
+ x_char_size
+ y_char_size
+ number_of_planes
+ bits_per_pixel
+ number_of_banks
+ memory_model
+ bank_size
+ number_of_image_pages
+ reserved0
+ red_mask_size
+ red_field_position
+ green_mask_size
+ green_field_position
+ blue_mask_size
+ blue_field_position
+ reserved_mask_size
+ reserved_field_position
+ direct_color_mode_info
+ phys_base
+ reserved1
+ reserved2
+ linear_bytes_per_scanline
+ banked_number_of_image_pages
+ linear_number_of_image_pages
+ linear_red_mask_size
+ linear_red_field_position
+ linear_green_mask_size
+ linear_green_field_position
+ linear_blue_mask_size
+ linear_blue_field_position
+ linear_reserved_mask_size
+ linear_reserved_field_position
+ max_pixel_clock
+ reserved3
* mode_attributes
* win_a_attributes
* win_b_attributes
* win_granularity
* win_size
* win_a_segment
* win_b_segment
* win_func
* bytes_per_scanline
* x_resolution
* y_resolution
* x_char_size
* y_char_size
* number_of_planes
* bits_per_pixel
* number_of_banks
* memory_model
* bank_size
* number_of_image_pages
* reserved0
* red_mask_size
* red_field_position
* green_mask_size
* green_field_position
* blue_mask_size
* blue_field_position
* reserved_mask_size
* reserved_field_position
* direct_color_mode_info
* phys_base
* reserved1
* reserved2
* linear_bytes_per_scanline
* banked_number_of_image_pages
* linear_number_of_image_pages
* linear_red_mask_size
* linear_red_field_position
* linear_green_mask_size
* linear_green_field_position
* linear_blue_mask_size
* linear_blue_field_position
* linear_reserved_mask_size
* linear_reserved_field_position
* max_pixel_clock
* reserved3

## Data Fields

### all VESA versions

- [l4\\_uint16\\_t mode\\_attributes](#)  
*Mode attributes.*
- [l4\\_uint8\\_t win\\_a\\_attributes](#)  
*Window A attributes.*

- [l4\\_uint8\\_t win\\_b\\_attributes](#)  
*Window B attributes.*
- [l4\\_uint16\\_t win\\_granularity](#)  
*Window granularity.*
- [l4\\_uint16\\_t win\\_size](#)  
*Window size.*
- [l4\\_uint16\\_t win\\_a\\_segment](#)  
*Window A start segment.*
- [l4\\_uint16\\_t win\\_b\\_segment](#)  
*Window B start segment.*
- [l4\\_uint32\\_t win\\_func](#)  
*Real mode pointer to window function.*
- [l4\\_uint16\\_t bytes\\_per\\_scanline](#)  
*Bytes per scan line.*

#### >= VESA version 1.2

- [l4\\_uint16\\_t x\\_resolution](#)  
*Horizontal resolution in pixels or characters.*
- [l4\\_uint16\\_t y\\_resolution](#)  
*Vertical resolution in pixels or characters.*
- [l4\\_uint8\\_t x\\_char\\_size](#)  
*Character cell width in pixels.*
- [l4\\_uint8\\_t y\\_char\\_size](#)  
*Character cell height in pixels.*
- [l4\\_uint8\\_t number\\_of\\_planes](#)  
*Number of memory planes.*
- [l4\\_uint8\\_t bits\\_per\\_pixel](#)  
*Bits per pixel.*
- [l4\\_uint8\\_t number\\_of\\_banks](#)  
*Number of banks.*
- [l4\\_uint8\\_t memory\\_model](#)  
*Memory model type.*
- [l4\\_uint8\\_t bank\\_size](#)  
*Bank size in KiB.*
- [l4\\_uint8\\_t number\\_of\\_image\\_pages](#)  
*Number of images.*
- [l4\\_uint8\\_t reserved0](#)  
*Reserved for page function.*

#### direct color

- [l4\\_uint8\\_t red\\_mask\\_size](#)  
*Size of direct color red mask in bits.*
- [l4\\_uint8\\_t red\\_field\\_position](#)  
*Bit position of LSB of red mask.*
- [l4\\_uint8\\_t green\\_mask\\_size](#)  
*Size of direct color green mask in bits.*
- [l4\\_uint8\\_t green\\_field\\_position](#)  
*Bit position of LSB of green mask.*
- [l4\\_uint8\\_t blue\\_mask\\_size](#)  
*Size of direct color blue mask in bits.*
- [l4\\_uint8\\_t blue\\_field\\_position](#)  
*Bit position of LSB of blue mask.*
- [l4\\_uint8\\_t reserved\\_mask\\_size](#)  
*Size of direct color reserved mask in bits.*
- [l4\\_uint8\\_t reserved\\_field\\_position](#)  
*Bit position of LSB of reserved mask.*



- [l4\\_uint8\\_t direct\\_color\\_mode\\_info](#)

*Direct color mode attributes.*

#### >= VESA version 2.0

- [l4\\_uint32\\_t phys\\_base](#)  
*Physical address for flat memory memory frame buffer.*
- [l4\\_uint32\\_t reserved1](#)  
*Reserved – always set to 0.*
- [l4\\_uint16\\_t reversed2](#)  
*Reserved – always set to 0.*

#### >= VESA version 3.0

- [l4\\_uint16\\_t linear\\_bytes\\_per\\_scanline](#)  
*Bytes per scan line for linear modes.*
- [l4\\_uint8\\_t banked\\_number\\_of\\_image\\_pages](#)  
*Number of images for banked modes.*
- [l4\\_uint8\\_t linear\\_number\\_of\\_image\\_pages](#)  
*Number of images for linear modes.*
- [l4\\_uint8\\_t linear\\_red\\_mask\\_size](#)  
*Size of direct color red mask (linear modes).*
- [l4\\_uint8\\_t linear\\_red\\_field\\_position](#)  
*Bit position of LSB of red mask (linear modes).*
- [l4\\_uint8\\_t linear\\_green\\_mask\\_size](#)  
*Size of direct color green mask (linear modes).*
- [l4\\_uint8\\_t linear\\_green\\_field\\_position](#)  
*Bit position of LSB of green mask (linear modes).*
- [l4\\_uint8\\_t linear\\_blue\\_mask\\_size](#)  
*Size of direct color blue mask (linear modes).*
- [l4\\_uint8\\_t linear\\_blue\\_field\\_position](#)  
*Bit position of LSB of blue mask (linear modes).*
- [l4\\_uint8\\_t linear\\_reserved\\_mask\\_size](#)  
*Size of direct color reserved mask (linear modes).*
- [l4\\_uint8\\_t linear\\_reserved\\_field\\_position](#)  
*Bit position of LSB of reserved mask (linear modes).*
- [l4\\_uint32\\_t max\\_pixel\\_clock](#)  
*Maximum pixel clock (in Hz) for graphics mode.*
- [l4\\_uint8\\_t reserved3](#) [190]  
*Reserved (padding).*

### 15.372.1 Detailed Description

VBE mode information.

Definition at line 125 of file [mb\\_info.h](#).

The documentation for this struct was generated from the following file:


- [l4/util/mb\\_info.h](#)

## 15.373 L4vbus::Device Class Reference


Device on a [L4vbus::Vbus](#).

```
#include <vbus>
```

Inheritance diagram for L4vbus::Device:



Collaboration diagram for L4vbus::Device:



## Public Member Functions

- **Device ( )**  
Construct a new vbus device using the NULL device `L4VBUS_NULL`.
- **Device (L4::Cap< Vbus > bus, l4vbus\_device\_handle\_t dev)**  
Construct a new vbus device using a device handle.
- **L4::Cap< Vbus > bus\_cap ( ) const**

- Access the *Vbus* capability of the underlying virtual bus.

  - `l4vbus_device_handle_t dev_handle () const`

Access the device handle of this device.
- `int device_by_hid (Device *child, char const *hid, int depth=L4VBUS_MAX_DEPTH, l4vbus_device_t *devinfo=0) const`

Find a device by the hardware interface identifier (HID).
- `int next_device (Device *child, int depth=L4VBUS_MAX_DEPTH, l4vbus_device_t *devinfo=0) const`

Find next child following *child*.
- `int device (l4vbus_device_t *devinfo) const`

Obtain detailed information about a *Vbus* device.
- `int get_resource (unsigned res_idx, l4vbus_resource_t *res) const`

Obtain the resource description of an individual device resource.
- `int is_compatible (char const *cid) const`

Check if the given device has a compatibility ID (CID) or HID that matches *cid*.
- `bool operator== (Device const &o) const`

Test if two devices are the same *Vbus* device.
- `bool operator!= (Device const &o) const`

Test if two *Vbus* devices are not the same.

## Public Member Functions inherited from `L4vbus::Pm< Device >`

- `int pm_suspend () const`

Suspend the device.
- `int pm_resume () const`

Resume the device.

## Protected Attributes

- `L4::Cap< Vbus > _bus`
- The *Vbus* capability where this device is located on.
- `l4vbus_device_handle_t _dev`
- The device handle for this device.

### 15.373.1 Detailed Description

`Device` on a `L4vbus::Vbus`.

Definition at line 83 of file `vbus`.

## 15.373.2 Constructor & Destructor Documentation

### 15.373.2.1 Device()

```
L4vbus::Device::Device (  
    L4::Cap< Vbus > bus,  
    l4vbus_device_handle_t dev) [inline]
```

Construct a new vbus device using a device handle.

Specifying the special root bus device handle [L4VBUS\\_ROOT\\_BUS](#) forms the root device of the corresponding vbus, see [Vbus::root](#).

#### Parameters

<i>bus</i>	The vbus capability where this device is assigned.
<i>dev</i>	The device handle of the device.

Definition at line 100 of file [vbus](#).

References [\\_bus](#), and [\\_dev](#).

## 15.373.3 Member Function Documentation

### 15.373.3.1 bus\_cap()

```
L4::Cap< Vbus > L4vbus::Device::bus_cap () const [inline]
```

Access the [Vbus](#) capability of the underlying virtual bus.

#### Returns


the capability to the underlying [Vbus](#).

Definition at line 107 of file [vbus](#).

References [\\_bus](#).

Referenced by [L4vbus::Pci\\_dev::cfg\\_read\(\)](#), [L4vbus::Pci\\_host\\_bridge::cfg\\_read\(\)](#), [L4vbus::Pci\\_dev::cfg\\_write\(\)](#), [L4vbus::Pci\\_host\\_bridge::cfg\\_write\(\)](#), [L4vbus::Pci\\_dev::irq\\_enable\(\)](#), and [L4vbus::Pci\\_host\\_bridge::irq\\_enable\(\)](#).

Here is the caller graph for this function:



### 15.373.3.2 dev\_handle()

```
l4vbus_device_handle_t L4vbus::Device::dev_handle () const [inline]
```

Access the device handle of this device.

#### Returns

the device handle for this device.

The device handle is used to directly address the device on its virtual bus.

Definition at line 116 of file `vbus`.

References `_dev`.

**15.373.3.3 device()**

```
int L4vbus::Device::device (
    l4vbus_device_t * devinfo) const [inline]
```

Obtain detailed information about a [Vbus](#) device.

**Parameters**

out	<i>devinfo</i>	Information structure which contains details about the device. The pointer might be NULL.
-----	----------------	---

**Return values**

0	Success.
-L4_ENODEV	No device with the given device handle <i>dev</i> could be found.

Definition at line 189 of file [vbus](#).

References [\\_bus](#), [\\_dev](#), and [l4vbus\\_get\\_device\(\)](#).

Here is the call graph for this function:

**15.373.3.4 device\_by\_hid()**

```
int L4vbus::Device::device_by_hid (
    Device * child,
    char const * hid,
    int depth = L4VBUS_MAX_DEPTH,
    l4vbus_device_t * devinfo = 0) const [inline]
```

Find a device by the hardware interface identifier (HID).

This function searches the vbus for a device with the given HID and returns a handle to the first matching device. The HID usually conforms to an ACPI HID or a Linux device tree compatible identifier.

It is possible to have multiple devices with the same HID on a vbus. In order to find all matching devices this function has to be called repeatedly with *child* pointing to the device found in the previous iteration. The iteration starts at *child* that might be any device node in the tree.

**Parameters**

in, out	<i>child</i>	Handle of the device from where in the device tree the search should start. To start searching from the beginning <i>child</i> must be initialized using the default ( <a href="#">L4VBUS_NULL</a> ). If a matching device is found, its handle is returned through this parameter.
	<i>hid</i>	HID of the device
	<i>depth</i>	Maximum depth for the recursive lookup
out	<i>devinfo</i>	<a href="#">Device</a> information structure (might be NULL)


**Return values**

$\geq 0$	A device with the given HID was found.
<code>-L4_ENOENT</code>	No device with the given HID could be found on the vbus.
<code>-L4_EINVAL</code>	Invalid or no HID provided.
<code>-L4_ENODEV</code>	Function called on a non-existing device.

Definition at line [148](#) of file [vbus](#).

References [\\_bus](#), [\\_dev](#), [Device\(\)](#), and [l4vbus\\_get\\_device\\_by\\_hid\(\)](#).

Here is the call graph for this function:

**15.373.3.5 get\_resource()**

```
int L4vbus::Device::get_resource (
    unsigned res_idx,
    l4vbus_resource_t * res) const [inline]
```

Obtain the resource description of an individual device resource.

**Parameters**

	<i>res_idx</i>	Index of the resource for which the resource description should be returned. The total number of resources for a device is available in the <a href="#">l4vbus_device_t</a> structure that is returned by <a href="#">L4vbus::Device::device_by_hid()</a> and <a href="#">L4vbus::Device::next_device()</a> .
--	----------------	---



out	res	Descriptor of the resource.
-----	-----	-----------------------------

This function returns the resource descriptor of an individual device resource selected by the `res_idx` parameter.


#### Return values

0	Success.
-L4_ENOENT	Invalid resource index <code>res_idx</code> .

Definition at line 209 of file [vbus](#).

References [\\_bus](#), [\\_dev](#), and [l4vbus\\_get\\_resource\(\)](#).

Here is the call graph for this function:



#### 15.373.3.6 is\_compatible()

```
int L4vbus::Device::is_compatible (
    char const * cid) const [inline]
```

Check if the given device has a compatibility ID (CID) or HID that matches `cid`.

#### Parameters

<i>cid</i>	the compatibility ID to test
------------	------------------------------


#### Returns

1 when the given ID (*cid*) matches this device, 0 when the given ID does not match, <0 on error.

Definition at line 223 of file [vbus](#).

References [\\_bus](#), [\\_dev](#), and [l4vbus\\_is\\_compatible\(\)](#).

Here is the call graph for this function:



### 15.373.3.7 next\_device()

```

int L4vbus::Device::next_device (
    Device * child,
    int depth = L4VBUS_MAX_DEPTH,
    l4vbus_device_t * devinfo = 0) const [inline]
  
```

Find next child following `child`.

#### Parameters

in, out	<i>child</i>	Handle of the device that precedes the device that shall be returned. To start from the beginning, <i>child</i> must be initialized with <a href="#">L4VBUS_NULL</a> ( <a href="#">Device::Device</a> ). If a device is found, its handle is returned through this parameter.
	<i>depth</i>	Depth to look for
out	<i>devinfo</i>	<a href="#">Device</a> information (might be NULL)


#### Returns

0 on success, else failure

Definition at line [171](#) of file [vbus](#).

References [\\_bus](#), [\\_dev](#), [Device\(\)](#), and [l4vbus\\_get\\_next\\_device\(\)](#).

Here is the call graph for this function:



### 15.373.3.8 operator!=(())

```
bool L4vbus::Device::operator!= (
    Device const & o) const [inline]
```

Test if two [Vbus](#) devices are not the same.

#### Returns

true if the two devices are different, false else.

Definition at line [239](#) of file [vbus](#).

References [\\_bus](#), [\\_dev](#), and [Device\(\)](#).

Here is the call graph for this function:



### 15.373.3.9 operator==(())

```
bool L4vbus::Device::operator== (
    Device const & o) const [inline]
```

Test if two devices are the same [Vbus](#) device.

#### Returns

true if the two devices are the same, false else.

Definition at line [230](#) of file [vbus](#).

References [\\_bus](#), [\\_dev](#), and [Device\(\)](#).

Here is the call graph for this function:



The documentation for this class was generated from the following file:


- [I4/vbus/vbus](#)

## 15.374 L4vbus::Gpio\_module Class Reference


A [Gpio\\_module](#) groups multiple GPIO pins together.

```
#include <vbus_gpio>
```

Inheritance diagram for L4vbus::Gpio\_module:



Collaboration diagram for L4vbus::Gpio\_module:



## Data Structures

- struct [Pin\\_slice](#)

*A slice of the pins provided by this module.*

## Public Member Functions

- int [setup](#) ([Pin\\_slice](#) const &mask, unsigned mode, unsigned value) const

- *Configure function of multiple GPIO pins at once.*  
• int [config\\_pad](#) ([Pin\\_slice](#) const &mask, unsigned func, unsigned value) const  
*Hardware specific configuration function for multiple GPIO pins.*
- int [get](#) (unsigned offset, unsigned \*data) const  
*Read values of multiple GPIO pins at once.*
- int [set](#) ([Pin\\_slice](#) const &mask, unsigned data)  
*Set multiple GPIO output pins at once.*
- [Gpio\\_pin](#) pin (unsigned pin) const  
*Get [Gpio\\_pin](#) for a specific pin of this [Gpio\\_module](#).*

## Public Member Functions inherited from [L4vbus::Device](#)

- [Device](#) ()  
*Construct a new vbus device using the NULL device [L4VBUS\\_NULL](#).*
- [Device](#) ([L4::Cap](#)< [Vbus](#) > bus, [l4vbus\\_device\\_handle\\_t](#) dev)  
*Construct a new vbus device using a device handle.*
- [L4::Cap](#)< [Vbus](#) > [bus\\_cap](#) () const  
*Access the [Vbus](#) capability of the underlying virtual bus.*
- [l4vbus\\_device\\_handle\\_t](#) [dev\\_handle](#) () const  
*Access the device handle of this device.*
- int [device\\_by\\_hid](#) ([Device](#) \*child, char const \*hid, int depth=[L4VBUS\\_MAX\\_DEPTH](#), [l4vbus\\_device\\_t](#) \*devinfo=0) const  
*Find a device by the hardware interface identifier (HID).*
- int [next\\_device](#) ([Device](#) \*child, int depth=[L4VBUS\\_MAX\\_DEPTH](#), [l4vbus\\_device\\_t](#) \*devinfo=0) const  
*Find next child following [child](#).*
- int [device](#) ([l4vbus\\_device\\_t](#) \*devinfo) const  
*Obtain detailed information about a [Vbus](#) device.*
- int [get\\_resource](#) (unsigned res\_idx, [l4vbus\\_resource\\_t](#) \*res) const  
*Obtain the resource description of an individual device resource.*
- int [is\\_compatible](#) (char const \*cid) const  
*Check if the given device has a compatibility ID (CID) or HID that matches [cid](#).*
- bool [operator==](#) ([Device](#) const &o) const  
*Test if two devices are the same [Vbus](#) device.*
- bool [operator!=](#) ([Device](#) const &o) const  
*Test if two [Vbus](#) devices are not the same.*

## Public Member Functions inherited from [L4vbus::Pm](#)< [Device](#) >

- int [pm\\_suspend](#) () const  
*Suspend the device.*
- int [pm\\_resume](#) () const  
*Resume the device.*

## Additional Inherited Members

## Protected Attributes inherited from [L4vbus::Device](#)

- [L4::Cap](#)< [Vbus](#) > [\\_bus](#)  
*The [Vbus](#) capability where this device is located on.*
- [l4vbus\\_device\\_handle\\_t](#) [\\_dev](#)  
*The device handle for this device.*

### 15.374.1 Detailed Description

A [Gpio\\_module](#) groups multiple GPIO pins together.

Definition at line 133 of file [vbus\\_gpio](#).

### 15.374.2 Member Function Documentation

#### 15.374.2.1 `config_pad()`

```
int L4vbus::Gpio_module::config_pad (  
    Pin_slice const & mask,  
    unsigned func,  
    unsigned value) const [inline]
```

Hardware specific configuration function for multiple GPIO pins.

#### Parameters

<i>mask</i>	Mask of GPIO pins to configure. A bit set to 1 configures this pin. A maximum of 32 pins can be configured at once. The real number depends on the hardware and the driver implementation.
<i>func</i>	Hardware specific configuration register, usually offset to the GPIO chip's base address.
<i>value</i>	Value which is written into the hardware specific configuration register for the specified pins


#### Returns

0 if OK, error code otherwise

Definition at line 185 of file [vbus\\_gpio](#).

References [L4vbus::Device::\\_bus](#), [L4vbus::Device::\\_dev](#), and [l4vbus\\_gpio\\_multi\\_config\\_pad\(\)](#).

Here is the call graph for this function:



### 15.374.2.2 `get()`

```
int L4vbus::Gpio_module::get (
    unsigned offset,
    unsigned * data) const [inline]
```

Read values of multiple GPIO pins at once.

#### Parameters

	<i>offset</i>	Pin corresponding to the LSB in <i>data</i> . Note: allowed may be hardware specific.
out	<i>data</i>	Each bit returns the value (0 or 1) for the corresponding GPIO pin. The value of pins that are not accessible is undefined.

#### Returns

0 if OK, error code otherwise

Definition at line 201 of file [vbus\\_gpio](#).

References [L4vbus::Device::\\_bus](#), [L4vbus::Device::\\_dev](#), and [l4vbus\\_gpio\\_multi\\_get\(\)](#).

Here is the call graph for this function:



### 15.374.2.3 `pin()`

```
Gpio_pin L4vbus::Gpio_module::pin (
    unsigned pin) const [inline]
```

Get [Gpio\\_pin](#) for a specific pin of this [Gpio\\_module](#).

#### Parameters

<i>pin</i>	GPIO pin number to get <a href="#">Gpio_pin</a> for.
------------	--



#### Returns


[Gpio\\_pin](#)

Definition at line 229 of file [vbus\\_gpio](#).


References [pin\(\)](#).

Referenced by [pin\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



#### 15.374.2.4 set()

```
int L4vbus::Gpio_module::set (  
    Pin\_slice const & mask,  
    unsigned data) [inline]
```

Set multiple GPIO output pins at once.

#### Parameters

<i>mask</i>	Mask of GPIO pins to set. A bit set to 1 selects this pin. A maximum of 32 pins can be set at once. The real number depends on the hardware and the driver implementation.
<i>data</i>	Each bit corresponds to the GPIO pin in <i>mask</i> . The value of each bit is written to the GPIO pin if its bit in <i>mask</i> is set.

**Returns**

0 if OK, error code otherwise

Definition at line 217 of file [vbus\\_gpio](#).

References [L4vbus::Device::\\_bus](#), [L4vbus::Device::\\_dev](#), and [l4vbus\\_gpio\\_multi\\_set\(\)](#).

Here is the call graph for this function:

**15.374.2.5 setup()**

```

int L4vbus::Gpio_module::setup (
    Pin_slice const & mask,
    unsigned mode,
    unsigned value) const [inline]
  
```

Configure function of multiple GPIO pins at once.

**Parameters**

<i>mask</i>	Mask of GPIO pins to configure. A bit set to 1 configures this pin. A maximum of 32 pins can be configured at once. The real number depends on the hardware and the driver implementation.
<i>mode</i>	GPIO function, see <a href="#">L4vbus_gpio_generic_func</a> for generic functions. Hardware specific functions must be provided in the lower 8 bits.
<i>value</i>	Optional value to set the GPIO pins to if they are configured as output pins


**Returns**

0 if OK, error code otherwise

Definition at line 166 of file [vbus\\_gpio](#).

References [L4vbus::Device::\\_bus](#), [L4vbus::Device::\\_dev](#), and [l4vbus\\_gpio\\_multi\\_setup\(\)](#).

Here is the call graph for this function:



The documentation for this class was generated from the following file:


- l4/vbus/vbus\_gpio

## 15.375 L4vbus::Gpio\_module::Pin\_slice Struct Reference

A slice of the pins provided by this module.

```
#include <vbus_gpio>
```

Collaboration diagram for L4vbus::Gpio\_module::Pin\_slice:



### 15.375.1 Detailed Description

A slice of the pins provided by this module.

Data type to specify a selection of pins for the 'multi' methods.

Definition at line [146](#) of file [vbus\\_gpio](#).

The documentation for this struct was generated from the following file:


- l4/vbus/vbus\_gpio

## 15.376 L4vbus::Gpio\_pin Class Reference


A GPIO pin.

```
#include <vbus_gpio>
```

Inheritance diagram for L4vbus::Gpio\_pin:



Collaboration diagram for L4vbus::Gpio\_pin:



## Public Member Functions

- `int` [get](#) () const  
*Read value of GPIO input pin.*
- `int` [set](#) (int value) const  
*Set GPIO output pin.*
- `int` [setup](#) (unsigned mode, unsigned value) const

- *Configure the function of a GPIO pin.*
- int `config_pull` (unsigned mode) const  
*Generic function to set pull up/down mode.*
- int `config_pad` (unsigned func, unsigned value) const  
*Hardware specific configuration function.*
- int `config_get` (unsigned func, unsigned \*value) const  
*Read hardware specific configuration.*
- int `to_irq` () const  
*Create IRQ for GPIO pin.*
- unsigned `pin` () const  
*Get pin number.*

## Public Member Functions inherited from `L4vbus::Device`

- `Device` ()  
*Construct a new vbus device using the NULL device `L4VBUS_NULL`.*
- `Device` (`L4::Cap`< `Vbus` > bus, `l4vbus_device_handle_t` dev)  
*Construct a new vbus device using a device handle.*
- `L4::Cap`< `Vbus` > `bus_cap` () const  
*Access the `Vbus` capability of the underlying virtual bus.*
- `l4vbus_device_handle_t` `dev_handle` () const  
*Access the device handle of this device.*
- int `device_by_hid` (`Device` \*child, char const \*hid, int depth=L4VBUS\_MAX\_DEPTH, `l4vbus_device_t` \*devinfo=0) const  
*Find a device by the hardware interface identifier (HID).*
- int `next_device` (`Device` \*child, int depth=L4VBUS\_MAX\_DEPTH, `l4vbus_device_t` \*devinfo=0) const  
*Find next child following `child`.*
- int `device` (`l4vbus_device_t` \*devinfo) const  
*Obtain detailed information about a `Vbus` device.*
- int `get_resource` (unsigned res\_idx, `l4vbus_resource_t` \*res) const  
*Obtain the resource description of an individual device resource.*
- int `is_compatible` (char const \*cid) const  
*Check if the given device has a compatibility ID (CID) or HID that matches `cid`.*
- bool `operator==` (`Device` const &o) const  
*Test if two devices are the same `Vbus` device.*
- bool `operator!=` (`Device` const &o) const  
*Test if two `Vbus` devices are not the same.*

## Public Member Functions inherited from `L4vbus::Pm`< `Device` >

- int `pm_suspend` () const  
*Suspend the device.*
- int `pm_resume` () const  
*Resume the device.*

## Additional Inherited Members

## Protected Attributes inherited from L4vbus::Device

- [L4::Cap< Vbus > \\_bus](#)  
The *Vbus* capability where this device is located on.
- [l4vbus\\_device\\_handle\\_t \\_dev](#)  
The device handle for this device.

## 15.376.1 Detailed Description

A GPIO pin.

Definition at line 26 of file [vbus\\_gpio](#).

## 15.376.2 Member Function Documentation

### 15.376.2.1 config\_get()

```
int L4vbus::Gpio_pin::config_get (
    unsigned func,
    unsigned * value) const [inline]
```

Read hardware specific configuration.

#### Parameters

	<i>func</i>	Hardware specific configuration register to read from. Usually this is an offset to the GPIO chip's base address.
out	<i>value</i>	The configuration value.

#### Returns

0 if OK, error code otherwise

Definition at line 102 of file [vbus\\_gpio](#).

References [L4vbus::Device::\\_bus](#), [L4vbus::Device::\\_dev](#), and [l4vbus\\_gpio\\_config\\_get\(\)](#).

Here is the call graph for this function:



### 15.376.2.2 config\_pad()

```
int L4vbus::Gpio_pin::config_pad (  
    unsigned func,  
    unsigned value) const [inline]
```

Hardware specific configuration function.

#### Parameters

<i>func</i>	Hardware specific configuration register, usually offset to the GPIO chip's base address
<i>value</i>	Value which is written into the hardware specific configuration register for the specified pin

#### Returns

0 if OK, error code otherwise

Definition at line 89 of file [vbus\\_gpio](#).

References [L4vbus::Device::\\_bus](#), [L4vbus::Device::\\_dev](#), and [l4vbus\\_gpio\\_config\\_pad\(\)](#).

Here is the call graph for this function:



### 15.376.2.3 config\_pull()

```
int L4vbus::Gpio_pin::config_pull (  
    unsigned mode) const [inline]
```

Generic function to set pull up/down mode.

#### Parameters

<i>mode</i>	mode for pull up/down resistors, see <a href="#">L4vbus_gpio_pull_modes</a>
-------------	---



**Returns**

0 if OK, error code otherwise

Definition at line 75 of file [vbus\\_gpio](#).

References [L4vbus::Device::\\_bus](#), [L4vbus::Device::\\_dev](#), and [l4vbus\\_gpio\\_config\\_pull\(\)](#).

Here is the call graph for this function:

**15.376.2.4 get()**

```
int L4vbus::Gpio_pin::get () const [inline]
```

Read value of GPIO input pin.

**Returns**

Value of GPIO pin (usually 0 or 1), negative error code otherwise.

Definition at line 38 of file [vbus\\_gpio](#).

References [L4vbus::Device::\\_bus](#), [L4vbus::Device::\\_dev](#), and [l4vbus\\_gpio\\_get\(\)](#).

Here is the call graph for this function:

**15.376.2.5 pin()**

```
unsigned L4vbus::Gpio_pin::pin () const [inline]
```

Get pin number.

**Returns**

GPIO pin number

Definition at line 122 of file [vbus\\_gpio](#).

### 15.376.2.6 set()

```
int L4vbus::Gpio_pin::set (  
    int value) const [inline]
```

Set GPIO output pin.

#### Parameters

<i>value</i>	Value to write to the GPIO pin (usually 0 or 1)
--------------	---

#### Returns

0 if OK, error code otherwise

Definition at line 49 of file [vbus\\_gpio](#).

References [L4vbus::Device::\\_bus](#), [L4vbus::Device::\\_dev](#), and [l4vbus\\_gpio\\_set\(\)](#).

Here is the call graph for this function:



### 15.376.2.7 setup()

```
int L4vbus::Gpio_pin::setup (  
    unsigned mode,  
    unsigned value) const [inline]
```

Configure the function of a GPIO pin.

#### Parameters

<i>mode</i>	GPIO function, see <a href="#">L4vbus_gpio_generic_func</a> for generic functions. Hardware specific functions must be provided in the lower 8 bits.
<i>value</i>	Optional value to set the GPIO pin to if it is configured as an output pin

**Returns**

0 if OK, error code otherwise

Definition at line 64 of file [vbus\\_gpio](#).

References [L4vbus::Device::\\_bus](#), [L4vbus::Device::\\_dev](#), and [l4vbus\\_gpio\\_setup\(\)](#).

Here is the call graph for this function:

**15.376.2.8 to\_irq()**

```
int L4vbus::Gpio_pin::to_irq () const [inline]
```

Create IRQ for GPIO pin.

**Returns**

IRQ number if OK, negative error code otherwise

Definition at line 112 of file [vbus\\_gpio](#).

References [L4vbus::Device::\\_bus](#), [L4vbus::Device::\\_dev](#), and [l4vbus\\_gpio\\_to\\_irq\(\)](#).

Here is the call graph for this function:



The documentation for this class was generated from the following file:


- `l4/vbus/vbus_gpio`

## 15.377 L4vbus::lcu Class Reference


[Vbus](#) Interrupt controller API.

```
#include <vbus>
```

Inheritance diagram for L4vbus::lcu:



Collaboration diagram for L4vbus::lcu:



## Public Types

- enum `Src_types` { `Src_dev_handle` = `L4VBUS_ICU_SRC_DEV_HANDLE` }  
Flags that can be used with the ICU on a vbus device.

## Public Member Functions

- int `vicu` (L4::Cap< L4::lcu > icu) const

Request an [L4::Icu](#) capability for this [Vbus](#)'s virtual ICU.

## Public Member Functions inherited from [L4vbus::Device](#)

- [Device](#) ()  
Construct a new vbus device using the NULL device [L4VBUS\\_NULL](#).
- [Device](#) ([L4::Cap](#)< [Vbus](#) > bus, [l4vbus\\_device\\_handle\\_t](#) dev)  
Construct a new vbus device using a device handle.
- [L4::Cap](#)< [Vbus](#) > [bus\\_cap](#) () const  
Access the [Vbus](#) capability of the underlying virtual bus.
- [l4vbus\\_device\\_handle\\_t dev\\_handle](#) () const  
Access the device handle of this device.
- int [device\\_by\\_hid](#) ([Device](#) \*child, char const \*hid, int depth=L4VBUS\_MAX\_DEPTH, [l4vbus\\_device\\_t](#) \*devinfo=0) const  
Find a device by the hardware interface identifier (HID).
- int [next\\_device](#) ([Device](#) \*child, int depth=L4VBUS\_MAX\_DEPTH, [l4vbus\\_device\\_t](#) \*devinfo=0) const  
Find next child following *child*.
- int [device](#) ([l4vbus\\_device\\_t](#) \*devinfo) const  
Obtain detailed information about a [Vbus](#) device.
- int [get\\_resource](#) (unsigned res\_idx, [l4vbus\\_resource\\_t](#) \*res) const  
Obtain the resource description of an individual device resource.
- int [is\\_compatible](#) (char const \*cid) const  
Check if the given device has a compatibility ID (CID) or HID that matches *cid*.
- bool [operator==](#) ([Device](#) const &o) const  
Test if two devices are the same [Vbus](#) device.
- bool [operator!=](#) ([Device](#) const &o) const  
Test if two [Vbus](#) devices are not the same.

## Public Member Functions inherited from [L4vbus::Pm](#)< [Device](#) >

- int [pm\\_suspend](#) () const  
Suspend the device.
- int [pm\\_resume](#) () const  
Resume the device.

## Additional Inherited Members

## Protected Attributes inherited from [L4vbus::Device](#)

- [L4::Cap](#)< [Vbus](#) > [\\_bus](#)  
The [Vbus](#) capability where this device is located on.
- [l4vbus\\_device\\_handle\\_t \\_dev](#)  
The device handle for this device.

## 15.377.1 Detailed Description

[Vbus](#) Interrupt controller API.

Every [Vbus](#) contains a virtual interrupt control unit that manages the IRQs of the devices on the bus. This class provides access to a capability to an [L4::Icu](#) object which can then be used to interface with the IRQs.

See also

[L4::Icu](#)

Definition at line 260 of file [vbus](#).

## 15.377.2 Member Enumeration Documentation

### 15.377.2.1 Src\_types

```
enum L4vbus::Icu::Src_types
```

Flags that can be used with the ICU on a vbus device.

#### Enumerator

Src_dev_handle	Flag to denote that the value should be interpreted as a device handle. This flag may be used in the <code>source</code> parameter in <a href="#">L4::Icu::msi_info()</a> to denote that the ICU should interpret the source ID as a device handle.
----------------	---

Definition at line 264 of file [vbus](#).

## 15.377.3 Member Function Documentation

### 15.377.3.1 vicu()

```
int L4vbus::Icu::vicu (  
    L4::Cap< L4::Icu > icu) const [inline]
```

Request an [L4::Icu](#) capability for this [Vbus](#)'s virtual ICU.

#### Parameters

<i>out</i>	<i>icu</i>	Capability slot where the <a href="#">L4::Icu</a> capability shall be stored.
------------	------------	---

#### Return values


0	Success.
---	----------

<i>otherwise</i>	IPC error.
------------------	------------

Definition at line 285 of file [vbus](#).

References [L4vbus::Device::\\_bus](#), [L4vbus::Device::\\_dev](#), [L4::Cap\\_base::cap\(\)](#), and [l4vbus\\_vicu\\_get\\_cap\(\)](#).

Here is the call graph for this function:



The documentation for this class was generated from the following file:

- `I4/vbus/vbus`


## 15.378 L4vbus::Pci\_dev Class Reference

A PCI device.


```
#include <vbus_pci>
```



Inheritance diagram for L4vbus::Pci\_dev:



Collaboration diagram for L4vbus::Pci\_dev:



## Public Member Functions

- `int cfg_read (l4_uint32_t reg, l4_uint32_t *value, l4_uint32_t width) const`  
Read from the device's vPCI configuration space.
- `int cfg_write (l4_uint32_t reg, l4_uint32_t value, l4_uint32_t width) const`  
Write to the device's vPCI configuration space.
- `int irq_enable (unsigned char *trigger, unsigned char *polarity) const`  
Enable the device's PCI interrupt.

## Public Member Functions inherited from L4vbus::Device

- **Device** ()  
*Construct a new vbus device using the NULL device L4VBUS\_NULL.*
- **Device** (L4::Cap< Vbus > bus, l4vbus\_device\_handle\_t dev)  
*Construct a new vbus device using a device handle.*
- **L4::Cap< Vbus > bus\_cap** () const  
*Access the Vbus capability of the underlying virtual bus.*
- **l4vbus\_device\_handle\_t dev\_handle** () const  
*Access the device handle of this device.*
- **int device\_by\_hid** (Device \*child, char const \*hid, int depth=L4VBUS\_MAX\_DEPTH, l4vbus\_device\_t \*devinfo=0) const  
*Find a device by the hardware interface identifier (HID).*
- **int next\_device** (Device \*child, int depth=L4VBUS\_MAX\_DEPTH, l4vbus\_device\_t \*devinfo=0) const  
*Find next child following child.*
- **int device** (l4vbus\_device\_t \*devinfo) const  
*Obtain detailed information about a Vbus device.*
- **int get\_resource** (unsigned res\_idx, l4vbus\_resource\_t \*res) const  
*Obtain the resource description of an individual device resource.*
- **int is\_compatible** (char const \*cid) const  
*Check if the given device has a compatibility ID (CID) or HID that matches cid.*
- **bool operator==** (Device const &o) const  
*Test if two devices are the same Vbus device.*
- **bool operator!=** (Device const &o) const  
*Test if two Vbus devices are not the same.*

## Public Member Functions inherited from L4vbus::Pm< Device >

- **int pm\_suspend** () const  
*Suspend the device.*
- **int pm\_resume** () const  
*Resume the device.*

## Additional Inherited Members

## Protected Attributes inherited from L4vbus::Device

- **L4::Cap< Vbus > \_bus**  
*The Vbus capability where this device is located on.*
- **l4vbus\_device\_handle\_t \_dev**  
*The device handle for this device.*

### 15.378.1 Detailed Description

A PCI device.

Definition at line 93 of file `vbus_pci`.

## 15.378.2 Member Function Documentation

### 15.378.2.1 `cfg_read()`

```
int L4vbus::Pci_dev::cfg_read (
    14_uint32_t reg,
    14_uint32_t * value,
    14_uint32_t width) const [inline]
```

Read from the device's vPCI configuration space.

#### Parameters

	<i>reg</i>	Register in configuration space to read
out	<i>value</i>	Value that has been read
	<i>width</i>	Width to read in bits (e.g. 8, 16, 32)


#### Returns

0 on success, else failure

Definition at line 105 of file `vbus_pci`.

References `L4vbus::Device::_dev`, `L4vbus::Device::bus_cap()`, and `l4vbus_pcidev_cfg_read()`.

Here is the call graph for this function:



### 15.378.2.2 `cfg_write()`

```
int L4vbus::Pci_dev::cfg_write (
    14_uint32_t reg,
    14_uint32_t value,
    14_uint32_t width) const [inline]
```

Write to the device's vPCI configuration space.

### Parameters

<i>reg</i>	Register in configuration space to write
<i>value</i>	Value to write
<i>width</i>	Width to write in bits (e.g. 8, 16, 32)


### Returns

0 on success, else failure

Definition at line 121 of file [vbus\\_pci](#).

References [L4vbus::Device::\\_dev](#), [L4vbus::Device::bus\\_cap\(\)](#), and [l4vbus\\_pcidev\\_cfg\\_write\(\)](#).

Here is the call graph for this function:



#### 15.378.2.3 irq\_enable()

```
int L4vbus::Pci_dev::irq_enable (  
    unsigned char * trigger,  
    unsigned char * polarity) const [inline]
```

Enable the device's PCI interrupt.

### Parameters

out	<i>trigger</i>	False if interrupt is level-triggered
out	<i>polarity</i>	True if interrupt is of low polarity


**Returns**

On success: Interrupt line to be used, else failure

Definition at line 137 of file [vbus\\_pci](#).

References [L4vbus::Device::\\_dev](#), [L4vbus::Device::bus\\_cap\(\)](#), and [l4vbus\\_pcidev\\_irq\\_enable\(\)](#).

Here is the call graph for this function:



The documentation for this class was generated from the following file:


- `l4/vbus/vbus_pci`

## 15.379 L4vbus::Pci\_host\_bridge Class Reference


A Pci host bridge.

```
#include <vbus_pci>
```

Inheritance diagram for L4vbus::Pci\_host\_bridge:



Collaboration diagram for L4vbus::Pci\_host\_bridge:



## Public Member Functions

- `int cfg_read (l4_uint32_t bus, l4_uint32_t devfn, l4_uint32_t reg, l4_uint32_t *value, l4_uint32_t width) const`  
Read from the vPCI configuration space using the PCI root bridge.
- `int cfg_write (l4_uint32_t bus, l4_uint32_t devfn, l4_uint32_t reg, l4_uint32_t value, l4_uint32_t width) const`  
Write to the vPCI configuration space using the PCI root bridge.



- int `irq_enable` (`l4_uint32_t` bus, `l4_uint32_t` devfn, int pin, unsigned char \*trigger, unsigned char \*polarity) const

*Enable PCI interrupt for a specific device using the PCI root bridge.*

## Public Member Functions inherited from L4vbus::Device

- **Device** ()  
*Construct a new vbus device using the NULL device `L4VBUS_NULL`.*
- **Device** (`L4::Cap`< `Vbus` > bus, `l4vbus_device_handle_t` dev)  
*Construct a new vbus device using a device handle.*
- `L4::Cap`< `Vbus` > `bus_cap` () const  
*Access the `Vbus` capability of the underlying virtual bus.*
- `l4vbus_device_handle_t` `dev_handle` () const  
*Access the device handle of this device.*
- int `device_by_hid` (`Device` \*child, char const \*hid, int depth=L4VBUS\_MAX\_DEPTH, `l4vbus_device_t` \*devinfo=0) const  
*Find a device by the hardware interface identifier (HID).*
- int `next_device` (`Device` \*child, int depth=L4VBUS\_MAX\_DEPTH, `l4vbus_device_t` \*devinfo=0) const  
*Find next child following `child`.*
- int `device` (`l4vbus_device_t` \*devinfo) const  
*Obtain detailed information about a `Vbus` device.*
- int `get_resource` (unsigned res\_idx, `l4vbus_resource_t` \*res) const  
*Obtain the resource description of an individual device resource.*
- int `is_compatible` (char const \*cid) const  
*Check if the given device has a compatibility ID (CID) or HID that matches `cid`.*
- bool `operator==` (`Device` const &o) const  
*Test if two devices are the same `Vbus` device.*
- bool `operator!=` (`Device` const &o) const  
*Test if two `Vbus` devices are not the same.*

## Public Member Functions inherited from L4vbus::Pm< Device >

- int `pm_suspend` () const  
*Suspend the device.*
- int `pm_resume` () const  
*Resume the device.*

## Additional Inherited Members

## Protected Attributes inherited from L4vbus::Device

- `L4::Cap`< `Vbus` > `_bus`  
*The `Vbus` capability where this device is located on.*
- `l4vbus_device_handle_t` `_dev`  
*The device handle for this device.*

### 15.379.1 Detailed Description

A Pci host bridge.

Definition at line 25 of file [vbus\\_pci](#).

### 15.379.2 Member Function Documentation

#### 15.379.2.1 `cfg_read()`

```
int L4vbus::Pci_host_bridge::cfg_read (
    14_uint32_t bus,
    14_uint32_t devfn,
    14_uint32_t reg,
    14_uint32_t * value,
    14_uint32_t width) const [inline]
```

Read from the vPCI configuration space using the PCI root bridge.

#### Parameters

	<i>bus</i>	Bus number
	<i>devfn</i>	<a href="#">Device</a> id (upper 16bit) and function (lower 16bit)
	<i>reg</i>	Register in configuration space to read
out	<i>value</i>	Value that has been read
	<i>width</i>	Width to read in bits (e.g. 8, 16, 32)


#### Returns

0 on success, else failure

Definition at line 39 of file [vbus\\_pci](#).

References [L4vbus::Device::\\_dev](#), [L4vbus::Device::bus\\_cap\(\)](#), and [l4vbus\\_pci\\_cfg\\_read\(\)](#).

Here is the call graph for this function:



### 15.379.2.2 cfg\_write()

```
int L4vbus::Pci_host_bridge::cfg_write (
    14_uint32_t bus,
    14_uint32_t devfn,
    14_uint32_t reg,
    14_uint32_t value,
    14_uint32_t width) const [inline]
```

Write to the vPCI configuration space using the PCI root bridge.

#### Parameters

<i>bus</i>	Bus number
<i>devfn</i>	<a href="#">Device</a> id (upper 16bit) and function (lower 16bit)
<i>reg</i>	Register in configuration space to write
<i>value</i>	Value to write
<i>width</i>	Width to write in bits (e.g. 8, 16, 32)


#### Returns

0 on success, else failure

Definition at line 58 of file [vbus\\_pci](#).

References [L4vbus::Device::\\_dev](#), [L4vbus::Device::bus\\_cap\(\)](#), and [l4vbus\\_pci\\_cfg\\_write\(\)](#).

Here is the call graph for this function:



### 15.379.2.3 irq\_enable()

```
int L4vbus::Pci_host_bridge::irq_enable (
    14_uint32_t bus,
    14_uint32_t devfn,
    int pin,
    unsigned char * trigger,
    unsigned char * polarity) const [inline]
```

Enable PCI interrupt for a specific device using the PCI root bridge.

#### Parameters

	<i>bus</i>	Bus number
	<i>devfn</i>	<a href="#">Device</a> id (upper 16bit) and function (lower 16bit)
	<i>pin</i>	Interrupt pin (normally as reported in configuration register INTR)
out	<i>trigger</i>	False if interrupt is level-triggered
out	<i>polarity</i>	True if interrupt is of low polarity


#### Returns

On success: Interrupt line to be used, else failure

Definition at line 79 of file [vbus\\_pci](#).

References [L4vbus::Device::\\_dev](#), [L4vbus::Device::bus\\_cap\(\)](#), and [l4vbus\\_pci\\_irq\\_enable\(\)](#).

Here is the call graph for this function:



The documentation for this class was generated from the following file:


- `l4/vbus/vbus_pci`

## 15.380 L4vbus::Pm< DEC > Class Template Reference


Power-management API mixin.

```
#include <vbus>
```

Inheritance diagram for L4vbus::Pm< DEC >:



Collaboration diagram for L4vbus::Pm< DEC >:



## Public Member Functions

- `int pm_suspend () const`  
*Suspend the device.*
- `int pm_resume () const`  
*Resume the device.*

### 15.380.1 Detailed Description

```
template<typename DEC>
class L4vbus::Pm< DEC >
```

Power-management API mixin.

Devices that inherit from this mixin provide an API to be suspended and resumed.

Definition at line 50 of file [vbus](#).

### 15.380.2 Member Function Documentation

#### 15.380.2.1 pm\_resume()

```
template<typename DEC>
int L4vbus::Pm< DEC >::pm_resume () const [inline]
```

Resume the device.

Switches the device from low-power mode to normal operation and restores the saved state.


#### Return values

0	Success.
---	----------

Definition at line 74 of file [vbus](#).

References [l4vbus\\_pm\\_resume\(\)](#).

Here is the call graph for this function:



### 15.380.2.2 pm\_suspend()

```
template<typename DEC>
int L4vbus::Pm< DEC >::pm_suspend () const [inline]
```

Suspend the device.

Saves the state of the device and puts it into a low-power mode.

#### Return values

0	Success.
---	----------

Definition at line 63 of file [vbus](#).

References [l4vbus\\_pm\\_suspend\(\)](#).

Here is the call graph for this function:



The documentation for this class was generated from the following file:


- `l4/vbus/vbus`

## 15.381 L4vbus::Vbus Class Reference

The virtual bus ([Vbus](#)) interface.


```
#include <vbus>
```

Inheritance diagram for L4vbus::Vbus:





Collaboration diagram for L4vbus::Vbus:



## Public Member Functions

- `int request_ioport (l4vbus_resource_t *res) const`  
Request the given IO port resource from the bus.
- `int release_ioport (l4vbus_resource_t *res) const`  
Release the given IO port resource from the bus.
- `Device root () const`

*Get the root device of the device tree of this bus.*

- `int assign_dma_domain` (unsigned domain\_id, unsigned flags, `L4::Cap< L4Re::Dma_space >` dma\_space) const

*Bind or unbind an `L4Re::Dma_space` to a DMA domain.*

- `int assign_dma_domain` (unsigned domain\_id, unsigned flags, `L4::Cap< L4::Task >` dma\_space) const

*Bind or unbind a kernel `DMA space` to a DMA domain.*

## Public Member Functions inherited from `L4Re::Dataspace`

- `l4_ret_t map` (Offset offset, Flags flags, Map\_addr local\_addr, Map\_addr min\_addr, Map\_addr max\_addr, `L4::Cap< L4::Task >` dst=`L4::Cap< L4::Task >::Invalid`) const noexcept

*Request a flexpage mapping from the dataspace.*

- `l4_ret_t map_region` (Offset offset, Flags flags, Map\_addr min\_addr, Map\_addr max\_addr, `L4::Cap< L4::Task >` dst=`L4::Cap< L4::Task >::Invalid`) const noexcept

*Map a part of a dataspace into a local memory area.*

- `l4_ret_t clear` (Offset offset, Size size)

*Clear parts of a dataspace.*

- `l4_ret_t allocate` (Offset offset, Size size)

*Allocate a range in the dataspace.*

- `l4_ret_t copy_in` (Offset dst\_offs, `L4::lpc::Cap< Dataspace >` src, Offset src\_offs, Size size)

*Copy contents from another dataspace.*

- `Size size` () const noexcept

*Get size of a dataspace.*

- `Flags flags` () const noexcept

*Get flags of the dataspace.*

- `l4_ret_t info` (`Stats *stats`)

*Get information on the dataspace.*

- `long map_info` (`l4_addr_t *start_addr`, `l4_addr_t *end_addr`)

*Get mapping range of dataspace.*

## Public Member Functions inherited from `L4::Kobject`

- `l4_msgtag_t dec_refcnt` (`l4_mword_t diff`, `l4_utcb_t *utcb=l4_utcb()`)

*Decrement the in kernel reference counter for the object.*

## Public Member Functions inherited from `L4Re::Inhibitor`

- `l4_ret_t acquire` (`l4_umword_t id`, `L4::lpc::String<>` reason)

*Acquire a specific inhibitor lock.*

- `l4_ret_t release` (`l4_umword_t id`)

*Release a specific inhibitor lock.*

- `l4_ret_t next_lock_info` (char \*name, unsigned len, `l4_mword_t current_id=-1`, `l4_utcb_t *utcb=l4_utcb()`)

*Get information for the next available inhibitor lock.*

## Public Member Functions inherited from L4Re::Event

- [l4\\_ret\\_t get\\_buffer](#) (L4::lpc::Out< L4::Cap< Dataspace > > ds)  
*Get event signal buffer.*
- [l4\\_ret\\_t get\\_num\\_streams](#) ()  
*Get number of event streams.*
- [l4\\_ret\\_t get\\_stream\\_info](#) (int idx, Event\_stream\_info \*info)  
*Get event stream infos.*
- [l4\\_ret\\_t get\\_stream\\_info\\_for\\_id](#) (l4\_umword\_t stream\_id, Event\_stream\_info \*info)  
*Get event stream infos.*
- [l4\\_ret\\_t get\\_axis\\_info](#) (l4\_umword\_t stream\_id, unsigned naxes, unsigned const \*axis, Event\_absinfo \*info) const noexcept  
*Get event stream axis infos.*
- [l4\\_ret\\_t get\\_stream\\_state\\_for\\_id](#) (l4\_umword\_t stream\_id, Event\_stream\_state \*state)  
*Get event stream state.*

## Public Member Functions inherited from L4::Icu

- [l4\\_msgtag\\_t bind](#) (unsigned irqnum, L4::Cap< Triggerable > irq, l4\_utcb\_t \*utcb=l4\_utcb()) noexcept  
*Bind an interrupt line of an interrupt controller to an interrupt object.*
- [l4\\_msgtag\\_t unbind](#) (unsigned irqnum, L4::Cap< Triggerable > irq, l4\_utcb\_t \*utcb=l4\_utcb()) noexcept  
*Remove binding of an interrupt line from the interrupt controller object.*
- [l4\\_msgtag\\_t info](#) (l4\_icu\_info\_t \*info, l4\_utcb\_t \*utcb=l4\_utcb()) noexcept  
*Get information about the ICU features.*
- [l4\\_msgtag\\_t msi\\_info](#) (l4\_umword\_t irqnum, l4\_uint64\_t source, l4\_icu\_msi\_info\_t \*msi\_info)  
*Get MSI info about IRQ.*
- [l4\\_msgtag\\_t mask](#) (unsigned irqnum, l4\_umword\_t \*label=0, l4\_timeout\_t to=L4\_IPC\_NEVER, l4\_utcb\_t \*utcb=l4\_utcb()) noexcept  
*Mask an IRQ line.*
- [l4\\_msgtag\\_t set\\_mode](#) (unsigned irqnum, l4\_umword\_t mode, l4\_utcb\_t \*utcb=l4\_utcb()) noexcept  
*Set interrupt mode.*

## Public Member Functions inherited from L4::Irq\_eoi

- [l4\\_msgtag\\_t unmask](#) (unsigned irqnum, l4\_umword\_t \*label=0, l4\_timeout\_t to=L4\_IPC\_NEVER, l4\_utcb\_t \*utcb=l4\_utcb()) noexcept  
*Unmask the given interrupt line.*

## Additional Inherited Members

## Public Types inherited from L4Re::Inhibitor

- enum { [Name\\_max](#) = 20 }

## Protected Types inherited from

### [L4::Kobject\\_3t< Vbus, L4Re::Dataspace, L4Re::Inhibitor, L4Re::Event >](#)

- typedef Vbus **Class**  
*The target interface type (inheriting from [Kobject\\_t](#)).*
- typedef Typeid::Iface< [PROTO\\_ANY](#), Vbus > **\_\_Iface**  
*The interface description for the derived class.*
- typedef Typeid::Merge\_list< Typeid::Iface\_list< **\_\_Iface** >, Typeid::Merge\_list< typename L4Re::↵  
 Dataspace::\_\_Iface\_list, Typeid::Merge\_list< typename L4Re::Inhibitor::\_\_Iface\_list, typename L4Re::↵  
 Event::\_\_Iface\_list > > > **\_\_Iface\_list**  
*The list of all RPC interfaces provided directly or through inheritance.*

## Protected Types inherited from

### [L4::Kobject\\_t< Dataspace, L4::Kobject, L4RE\\_PROTO\\_DATASPACE, L4::Type\\_info::Demand\\_t< 1 > >](#)

- typedef Dataspace **Class**  
*The target interface type (inheriting from [Kobject\\_t](#)).*
- typedef Typeid::Iface< [PROTO](#), Dataspace > **\_\_Iface**  
*The interface description for the derived class.*
- typedef Typeid::Merge\_list< Typeid::Iface\_list< **\_\_Iface** >, typename L4::Kobject::\_\_Iface\_list > **\_\_Iface\_list**  
*The list of all RPC interfaces provided directly or through inheritance.*

## Protected Types inherited from

### [L4::Kobject\\_t< Inhibitor, L4::Kobject, L4RE\\_PROTO\\_INHIBITOR >](#)

- typedef Inhibitor **Class**  
*The target interface type (inheriting from [Kobject\\_t](#)).*
- typedef Typeid::Iface< [PROTO](#), Inhibitor > **\_\_Iface**  
*The interface description for the derived class.*
- typedef Typeid::Merge\_list< Typeid::Iface\_list< **\_\_Iface** >, typename L4::Kobject::\_\_Iface\_list > **\_\_Iface\_list**  
*The list of all RPC interfaces provided directly or through inheritance.*

## Protected Types inherited from [L4::Kobject\\_t< Event, L4::lcu, L4RE\\_PROTO\\_EVENT >](#)

- typedef Event **Class**  
*The target interface type (inheriting from [Kobject\\_t](#)).*
- typedef Typeid::Iface< [PROTO](#), Event > **\_\_Iface**  
*The interface description for the derived class.*
- typedef Typeid::Merge\_list< Typeid::Iface\_list< **\_\_Iface** >, typename L4::lcu::\_\_Iface\_list > **\_\_Iface\_list**  
*The list of all RPC interfaces provided directly or through inheritance.*

## Protected Types inherited from

### [L4::Kobject\\_t< lcu, Irq\\_eoi, L4\\_PROTO\\_IRQ, Type\\_info::Demand\\_t< 1 > >](#)

- typedef lcu **Class**  
*The target interface type (inheriting from [Kobject\\_t](#)).*
- typedef Typeid::Iface< [PROTO](#), lcu > **\_\_Iface**  
*The interface description for the derived class.*
- typedef Typeid::Merge\_list< Typeid::Iface\_list< **\_\_Iface** >, typename Irq\_eoi::\_\_Iface\_list > **\_\_Iface\_list**  
*The list of all RPC interfaces provided directly or through inheritance.*

**Protected Member Functions inherited from****L4::Kobject\_3t< Vbus, L4Re::Dataspace, L4Re::Inhibitor, L4Re::Event >**

- **L4::Cap< Class > c ()** const noexcept

*Get the capability to ourselves.***Protected Member Functions inherited from****L4::Kobject\_t< Dataspace, L4::Kobject, L4RE\_PROTO\_DATASPACE, L4::Type\_info::Demand\_t< 1 > >**

- **L4::Cap< Class > c ()** const noexcept

*Get the capability to ourselves.***Protected Member Functions inherited from L4::Kobject**

- **l4\_cap\_idx\_t cap ()** const noexcept

*Return capability selector.***Protected Member Functions inherited from****L4::Kobject\_t< Inhibitor, L4::Kobject, L4RE\_PROTO\_INHIBITOR >**

- **L4::Cap< Class > c ()** const noexcept

*Get the capability to ourselves.***Protected Member Functions inherited from****L4::Kobject\_t< Event, L4::lcu, L4RE\_PROTO\_EVENT >**

- **L4::Cap< Class > c ()** const noexcept

*Get the capability to ourselves.***Protected Member Functions inherited from****L4::Kobject\_t< lcu, Irq\_eoi, L4\_PROTO\_IRQ, Type\_info::Demand\_t< 1 > >**

- **L4::Cap< Class > c ()** const noexcept

*Get the capability to ourselves.***Static Protected Member Functions inherited from****L4::Kobject\_3t< Vbus, L4Re::Dataspace, L4Re::Inhibitor, L4Re::Event >**

- static void **\_\_check\_protocols\_\_ ()** noexcept

*Helper to check for protocol conflicts.***Static Protected Member Functions inherited from****L4::Kobject\_t< Dataspace, L4::Kobject, L4RE\_PROTO\_DATASPACE, L4::Type\_info::Demand\_t< 1 > >**

- static void **\_\_check\_protocols\_\_ ()** noexcept

*Helper to check for protocol conflicts.*

**Static Protected Member Functions inherited from****[L4::Kobject\\_t< Inhibitor, L4::Kobject, L4RE\\_PROTO\\_INHIBITOR >](#)**

- static void **\_\_check\_protocols\_\_** () noexcept  
*Helper to check for protocol conflicts.*

**Static Protected Member Functions inherited from****[L4::Kobject\\_t< Event, L4::lcu, L4RE\\_PROTO\\_EVENT >](#)**

- static void **\_\_check\_protocols\_\_** () noexcept  
*Helper to check for protocol conflicts.*

**Static Protected Member Functions inherited from****[L4::Kobject\\_t< lcu, Irq\\_eoi, L4\\_PROTO\\_IRQ, Type\\_info::Demand\\_t< 1 > >](#)**

- static void **\_\_check\_protocols\_\_** () noexcept  
*Helper to check for protocol conflicts.*

**15.381.1 Detailed Description**

The virtual bus ([Vbus](#)) interface.

See also

[L4Re Vbus API](#)

Definition at line [298](#) of file [vbus](#).

**15.381.2 Member Function Documentation****15.381.2.1 [assign\\_dma\\_domain\(\)](#) [1/2]**

```
int L4vbus::Vbus::assign_dma_domain (
    unsigned domain_id,
    unsigned flags,
    L4::Cap< L4::Task > dma_space) const [inline]
```

Bind or unbind a kernel [DMA space](#) to a DMA domain.

**Parameters**

<i>domain_id</i>	DMA domain ID (resource address of DMA domain found on the vBUS). If the value is ~0U the DMA space of the whole vBUS is used.
<i>flags</i>	A combination of <a href="#">L4vbus_dma_domain_assign_flags</a> .
<i>dma_space</i>	The DMA space capability to bind or unbind, this must be a kernel <a href="#">DMA space</a> ( <a href="#">L4::Task</a> created with L4_PROTO_DMA_SPACE)


**Return values**

<i>0</i>	Operation completed successfully.
<i>-L4_ENOENT</i>	The vbus does not support a global DMA domain or no DMA domain could be found.
<i>-L4_EINVAL</i>	Invalid argument used.
<i>-L4_EBUSY</i>	DMA domain is already active, this means another DMA space is already assigned.

Definition at line 382 of file [vbus](#).

References [L4::Cap\\_base::cap\(\)](#), [L4::Kobject::cap\(\)](#), [L4Re::Dataspace::flags\(\)](#), [l4vbus\\_assign\\_dma\\_domain\(\)](#), [L4VBUS\\_DMAD\\_KERNEL\\_DMA\\_SPACE](#), and [L4VBUS\\_DMAD\\_L4RE\\_DMA\\_SPACE](#).

Here is the call graph for this function:

**15.381.2.2 assign\_dma\_domain() [2/2]**

```

int L4vbus::Vbus::assign_dma_domain (
    unsigned domain_id,
    unsigned flags,
    L4::Cap< L4Re::Dma_space > dma_space) const [inline]

```

Bind or unbind an [L4Re::Dma\\_space](#) to a DMA domain.

**Parameters**

<i>domain_id</i>	DMA domain ID (resource address of DMA domain found on the vBUS). If the value is ~0U the DMA space of the whole vBUS is used.
<i>flags</i>	A combination of <a href="#">L4vbus_dma_domain_assign_flags</a> .
<i>dma_space</i>	The DMA space capability to bind or unbind, this must be an <a href="#">L4Re::Dma_space</a>


**Return values**

<i>0</i>	Operation completed successfully.
<i>-L4_ENOENT</i>	The vbus does not support a global DMA domain or no DMA domain could be found.
<i>-L4_EINVAL</i>	Invalid argument used.
<i>-L4_EBUSY</i>	DMA domain is already active, this means another DMA space is already assigned.

Definition at line 357 of file [vbus](#).

References [L4::Cap\\_base::cap\(\)](#), [L4::Kobject::cap\(\)](#), [L4Re::Dataspace::flags\(\)](#), [l4vbus\\_assign\\_dma\\_domain\(\)](#), [L4VBUS\\_DMAD\\_KERNEL\\_DMA\\_SPACE](#), and [L4VBUS\\_DMAD\\_L4RE\\_DMA\\_SPACE](#).

Here is the call graph for this function:



### 15.381.2.3 release\_ioport()

```
int L4vbus::Vbus::release_ioport (
    l4vbus_resource_t * res) const [inline]
```

Release the given IO port resource from the bus.

#### Parameters

in	res	The IO port resource to be released from the bus.
----	-----	---


#### Returns

>=0 on success, <0 on error.

Definition at line 323 of file [vbus](#).

References [L4::Kobject::cap\(\)](#), and [l4vbus\\_release\\_ioport\(\)](#).

Here is the call graph for this function:





#### 15.381.2.4 request\_ioport()

```
int L4vbus::Vbus::request_ioport (
    l4vbus_resource_t * res) const [inline]
```

Request the given IO port resource from the bus.

##### Parameters

in	res	The IO port resource to be requested from the bus.
----	-----	--


##### Return values

0	Success.
-L4_EINVAL	Resource is not an IO port resource.
-L4_ENOENT	No matching IO port resource found.

Definition at line 311 of file [vbus](#).

References [L4::Kobject::cap\(\)](#), and [l4vbus\\_request\\_ioport\(\)](#).

Here is the call graph for this function:



#### 15.381.2.5 root()

```
Device L4vbus::Vbus::root () const [inline]
```

Get the root device of the device tree of this bus.

The root device is usually the starting point for iterating the bus, see [Device::next\\_device](#).

### Returns

A [Vbus](#) device representing the root of the device tree.

Definition at line [336](#) of file [vbus](#).

References [L4::Kobject::cap\(\)](#), and [L4VBUS\\_ROOT\\_BUS](#).

Here is the call graph for this function:



The documentation for this class was generated from the following file:


- `I4/vbus/vbus`

## 15.382 I4vbus\_device\_t Struct Reference

Detailed information about a vbus device.

```
#include <vbus_types.h>
```

Collaboration diagram for `I4vbus_device_t`:



## Data Fields

- [l4\\_uint32\\_t](#) **type**  
*Bitfield of supported sub-interfaces, see [l4vbus\\_iface\\_type\\_t](#).*
- char **name** [L4VBUS\_DEV\_NAME\_LEN]  
*Name.*
- unsigned **num\_resources**  
*Number of resources for this device.*
- unsigned **flags**  
*Flags, see [l4vbus\\_device\\_flags\\_t](#).*

### 15.382.1 Detailed Description

Detailed information about a vbus device.

Definition at line 80 of file [vbus\\_types.h](#).

The documentation for this struct was generated from the following file:

- [l4/vbus/vbus\\_types.h](#)

## 15.383 l4vbus\_resource\_t Struct Reference

Description of a single vbus resource.

```
#include <vbus_types.h>
```

Collaboration diagram for l4vbus\_resource\_t:

l4vbus_resource_t	
+	type
+	flags
+	start
+	end
+	provider
+	id

## Data Fields

- [l4\\_uint16\\_t](#) **type**  
*Resource type, see [l4vbus\\_resource\\_type\\_t](#).*
- [l4\\_uint16\\_t](#) **flags**  
*Flags.*
- [l4vbus\\_paddr\\_t](#) **start**  
*Start of resource range.*
- [l4vbus\\_paddr\\_t](#) **end**  
*End of resource range (inclusive).*
- [l4vbus\\_device\\_handle\\_t](#) **provider**  
*Device handle of the provider of the resource.*
- [l4\\_uint32\\_t](#) **id**  
*Resource ID (4 bytes), usually a 4 letter ASCII name is used.*

### 15.383.1 Detailed Description

Description of a single vbus resource.

Definition at line 23 of file [vbus\\_types.h](#).

The documentation for this struct was generated from the following file:


- [l4/vbus/vbus\\_types.h](#)

## 15.384 L4vcpu::State Class Reference

C++ implementation of state word in the vCPU area.

```
#include <vcpu>
```

Collaboration diagram for L4vcpu::State:



## Public Member Functions

- [State](#) (unsigned v)  
*Initialize state.*
- void [add](#) (unsigned bits) throw ()  
*Add flags.*
- void [clear](#) (unsigned bits) throw ()  
*Clear flags.*
- void [set](#) (unsigned v) throw ()  
*Set flags.*

## 15.384.1 Detailed Description

C++ implementation of state word in the vCPU area.

Definition at line 24 of file [vcpu](#).

## 15.384.2 Constructor & Destructor Documentation

### 15.384.2.1 State()

```
L4vcpu::State::State (  
    unsigned v) [inline], [explicit]
```

Initialize state.

#### Parameters

<i>v</i>	Initial state.
----------	----------------

Definition at line 34 of file [vcpu](#).

## 15.384.3 Member Function Documentation

### 15.384.3.1 add()

```
void L4vcpu::State::add (  
    unsigned bits) throw ( ) [inline]
```

Add flags.

#### Parameters

<i>bits</i>	Bits to add to the word.
-------------	--------------------------

Definition at line 41 of file [vcpu](#).

### 15.384.3.2 clear()

```
void L4vcpu::State::clear (
    unsigned bits) throw ( )    [inline]
```

Clear flags.

#### Parameters

<i>bits</i>	Bits to clear in the word.
-------------	----------------------------

Definition at line 48 of file [vcpu](#).

### 15.384.3.3 set()

```
void L4vcpu::State::set (
    unsigned v) throw ( )    [inline]
```

Set flags.

#### Parameters

<i>v</i>	Set the word to the value of v.
----------	---------------------------------

Definition at line 55 of file [vcpu](#).

The documentation for this class was generated from the following file:


- [l4/vcpu/vcpu](#)

## 15.385 L4vcpu::Vcpu Class Reference


C++ implementation of the vCPU save state area.

```
#include <vcpu>
```

Inheritance diagram for L4vcpu::Vcpu:



Collaboration diagram for L4vcpu::Vcpu:



## Public Member Functions

- void **irq\_disable** () throw ()  
*Disable the vCPU for event delivery.*
- unsigned **irq\_disable\_save** () throw ()  
*Disable the vCPU for event delivery and return previous state.*
- **State** \* **state** () throw ()



- Get state word.*

  - [State state](#) () const throw ()

*Get state word.*
- [State \\* saved\\_state](#) () throw ()

*Get saved\_state word.*
- [State saved\\_state](#) () const throw ()

*Get saved\_state word.*
- [l4\\_uint16\\_t sticky\\_flags](#) () const throw ()

*Get sticky flags.*
- void [irq\\_enable](#) ([l4\\_utcb\\_t](#) \*utcb, [l4vcpu\\_event\\_hndl\\_t](#) do\_event\_work\_cb, [l4vcpu\\_setup\\_ipc\\_t](#) setup\_ipc) throw ()

*Enable the vCPU for event delivery.*
- void [irq\\_restore](#) (unsigned s, [l4\\_utcb\\_t](#) \*utcb, [l4vcpu\\_event\\_hndl\\_t](#) do\_event\_work\_cb, [l4vcpu\\_setup\\_ipc\\_t](#) setup\_ipc) throw ()

*Restore a previously saved IRQ/event state.*
- void [wait\\_for\\_event](#) ([l4\\_utcb\\_t](#) \*utcb, [l4vcpu\\_event\\_hndl\\_t](#) do\_event\_work\_cb, [l4vcpu\\_setup\\_ipc\\_t](#) setup\_ipc) throw ()

*Wait for event.*
- void [task](#) ([L4::Cap](#)< [L4::Task](#) > const task=[L4::Cap](#)< [L4::Task](#) >::Invalid) throw ()

*Set the task of the vCPU.*
- int [is\\_page\\_fault\\_entry](#) () const

*Return whether the entry reason was a page fault.*
- int [is\\_irq\\_entry](#) () const

*Return whether the entry reason was an IRQ/IPC message.*
- [l4\\_vcpu\\_regs\\_t](#) \* r () throw ()

*Return pointer to register state.*
- [l4\\_vcpu\\_regs\\_t](#) const \* r () const throw ()

*Return pointer to register state.*
- [l4\\_vcpu\\_ipc\\_regs\\_t](#) \* i () throw ()

*Return pointer to IPC state.*
- [l4\\_vcpu\\_ipc\\_regs\\_t](#) const \* i () const throw ()

*Return pointer to IPC state.*
- void [entry\\_sp](#) ([l4\\_umword\\_t](#) sp)

*Set vCPU entry stack pointer.*
- void [entry\\_ip](#) ([l4\\_umword\\_t](#) ip)

*Set vCPU entry instruction pointer.*
- void [print\\_state](#) (const char \*prefix="") const throw ()

*Print the state of the vCPU.*

### Static Public Member Functions

- static int [ext\\_alloc](#) ([Vcpu](#) \*\*vcpu, [l4\\_addr\\_t](#) \*ext\_state, [L4::Cap](#)< [L4::Task](#) > task=[L4Re::Env::env](#)() ->task(), [L4::Cap](#)< [L4Re::Rm](#) > rm=[L4Re::Env::env](#)() ->rm()) throw ()

*Allocate state area for an extended vCPU.*
- static [Vcpu](#) \* [cast](#) (void \*x) throw ()

*Cast a void pointer to a class pointer.*
- static [Vcpu](#) \* [cast](#) ([l4\\_addr\\_t](#) x) throw ()

*Cast an address to a class pointer.*

### 15.385.1 Detailed Description

C++ implementation of the vCPU save state area.

Definition at line 65 of file [vcpu](#).

### 15.385.2 Member Function Documentation

#### 15.385.2.1 `cast()` [1/2]

```
Vcpu * L4vcpu::Vcpu::cast (
    l4\_addr\_t x) throw ( )    [inline], [static]
```

Cast an address to a class pointer.

##### Parameters

<i>x</i>	Pointer.
----------	----------

##### Returns

Pointer to [Vcpu](#) class.

Definition at line 269 of file [vcpu](#).

#### 15.385.2.2 `cast()` [2/2]

```
Vcpu * L4vcpu::Vcpu::cast (
    void * x) throw ( )    [inline], [static]
```

Cast a void pointer to a class pointer.

##### Parameters

<i>x</i>	Pointer.
----------	----------

**Returns**

Pointer to [Vcpu](#) class.

Definition at line [259](#) of file [vcpu](#).

References [cast\(\)](#).

Referenced by [cast\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:

**15.385.2.3 entry\_ip()**

```
void L4vcpu::Vcpu::entry_ip (  
    14_umword_t ip) [inline]
```

Set vCPU entry instruction pointer.

**Parameters**

<i>ip</i>	Instruction pointer address to set.
-----------	-------------------------------------

Definition at line [232](#) of file [vcpu](#).

References [l4\\_vcpu\\_state\\_t::entry\\_ip](#).

### 15.385.2.4 entry\_sp()

```
void L4vcpu::Vcpu::entry_sp (
    l4_umword_t sp) [inline]
```

Set vCPU entry stack pointer.

#### Parameters

<i>sp</i>	Stack pointer address to set.
-----------	-------------------------------

#### Note

The value is only used when entering from a user-task.

Definition at line 225 of file `vcpu`.

References `l4_vcpu_state_t::entry_sp`.

### 15.385.2.5 ext\_alloc()

```
int L4vcpu::Vcpu::ext_alloc (
    Vcpu ** vcpu,
    l4_addr_t * ext_state,
    L4::Cap< L4::Task > task = L4Re::Env::env() ->task(),
    L4::Cap< L4Re::Rm > rm = L4Re::Env::env() ->rm() throw ( ) [static]
```

Allocate state area for an extended vCPU.

#### Parameters


out	<i>vcpu</i>	Allocated vcpu-state area.
out	<i>ext_state</i>	Allocated extended vcpu-state area.
	<i>task</i>	Task to use for allocation, defaults to own task.
	<i>rm</i>	Region manager to use for allocation defaults to standard region manager.

#### Returns

0 for success, error code otherwise

References `L4Re::Env::env()`, and `task()`.

Here is the call graph for this function:



### 15.385.2.6 i() [1/2]

```
l4_vcpu_ipc_regs_t * L4vcpu::Vcpu::i () throw ( ) [inline]
```

Return pointer to IPC state.

#### Returns

Pointer to IPC state.

Definition at line 209 of file `vcpu`.

References `l4_vcpu_state_t::i`.

### 15.385.2.7 i() [2/2]

```
l4_vcpu_ipc_regs_t const * L4vcpu::Vcpu::i () const throw ( ) [inline]
```

Return pointer to IPC state.

#### Returns

Pointer to IPC state.

Definition at line 216 of file `vcpu`.

References `l4_vcpu_state_t::i`.

### 15.385.2.8 irq\_disable\_save()

```
unsigned L4vcpu::Vcpu::irq_disable_save () throw ( ) [inline]
```

Disable the vCPU for event delivery and return previous state.


#### Returns

IRQ state before disabling IRQs.

Definition at line 78 of file `vcpu`.

References `l4vcpu_irq_disable_save()`.

Here is the call graph for this function:



### 15.385.2.9 irq\_enable()

```
void L4vcpu::Vcpu::irq_enable (
    l4_utcb_t * utcb,
    l4vcpu_event_hndl_t do_event_work_cb,
    l4vcpu_setup_ipc_t setup_ipc) throw ( )    [inline]
```

Enable the vCPU for event delivery.


#### Parameters

<i>utcb</i>	The UTCB to use.
<i>do_event_work_cb</i>	Call-back function that is called in case an event (such as an interrupt) is pending.
<i>setup_ipc</i>	Call-back function that is called before an IPC operation is called, and before event delivery is enabled.

Definition at line 135 of file [vcpu](#).

References [l4vcpu\\_irq\\_enable\(\)](#).

Here is the call graph for this function:



### 15.385.2.10 irq\_restore()

```
void L4vcpu::Vcpu::irq_restore (
    unsigned s,
    l4_utcb_t * utcb,
    l4vcpu_event_hndl_t do_event_work_cb,
    l4vcpu_setup_ipc_t setup_ipc) throw ( )    [inline]
```

Restore a previously saved IRQ/event state.

#### Parameters

<i>s</i>	IRQ state to be restored.
<i>utcb</i>	The UTCB to use.
<i>do_event_work_cb</i>	Call-back function that is called in case an event (such as an interrupt) is pending.
<i>setup_ipc</i>	Call-back function that is called before an IPC operation is called, and before event delivery is enabled.

Definition at line 150 of file [vcpu](#).

References [l4vcpu\\_irq\\_restore\(\)](#).

Here is the call graph for this function:



### 15.385.2.11 is\_irq\_entry()

```
int L4vcpu::Vcpu::is_irq_entry () const [inline]
```


Return whether the entry reason was an IRQ/IPC message.

return 0 if not, !=0 otherwise.

Definition at line 188 of file [vcpu](#).

References [l4vcpu\\_is\\_irq\\_entry\(\)](#).

Here is the call graph for this function:



### 15.385.2.12 is\_page\_fault\_entry()

```
int L4vcpu::Vcpu::is_page_fault_entry () const [inline]
```


Return whether the entry reason was a page fault.

return 0 if not, !=0 otherwise.

Definition at line 181 of file [vcpu](#).

References [l4vcpu\\_is\\_page\\_fault\\_entry\(\)](#).

Here is the call graph for this function:



#### 15.385.2.13 `r()` [1/2]

```
l4_vcpu_regs_t * L4vcpu::Vcpu::r () throw ( ) [inline]
```

Return pointer to register state.

##### Returns

Pointer to register state.

Definition at line 195 of file `vcpu`.

References `l4_vcpu_state_t::r`.

#### 15.385.2.14 `r()` [2/2]

```
l4_vcpu_regs_t const * L4vcpu::Vcpu::r () const throw ( ) [inline]
```

Return pointer to register state.

##### Returns

Pointer to register state.

Definition at line 202 of file `vcpu`.

References `l4_vcpu_state_t::r`.

#### 15.385.2.15 `saved_state()` [1/2]

```
State * L4vcpu::Vcpu::saved_state () throw ( ) [inline]
```

Get `saved_state` word.

##### Returns

Pointer to `saved_state` word in the vCPU

Definition at line 106 of file `vcpu`.

References `l4_vcpu_state_t::saved_state`.



**15.385.2.16 saved\_state()** [2/2]

```
State L4vcpu::Vcpu::saved_state () const throw ( )    [inline]
```

Get saved\_state word.

**Returns**

Pointer to saved\_state word in the vCPU

Definition at line 116 of file [vcpu](#).

References [l4\\_vcpu\\_state\\_t::saved\\_state](#).

**15.385.2.17 state()** [1/2]

```
State * L4vcpu::Vcpu::state () throw ( )    [inline]
```

Get state word.

**Returns**

Pointer to state word in the vCPU

Definition at line 88 of file [vcpu](#).

References [l4\\_vcpu\\_state\\_t::state](#).

**15.385.2.18 state()** [2/2]

```
State L4vcpu::Vcpu::state () const throw ( )    [inline]
```

Get state word.

**Returns**

Pointer to state word in the vCPU

Definition at line 99 of file [vcpu](#).

References [l4\\_vcpu\\_state\\_t::state](#).

**15.385.2.19 task()**

```
void L4vcpu::Vcpu::task (
    L4::Cap< L4::Task > const task = L4::Cap<L4::Task>::Invalid) throw ( )    [inline]
```

Set the task of the vCPU.

**Parameters**

<i>task</i>	Task to set, defaults to invalid task.
-------------	--

Definition at line 174 of file [vcpu](#).


References [L4::Cap\\_base::Invalid](#), [task\(\)](#), and [l4\\_vcpu\\_state\\_t::user\\_task](#).

Referenced by [ext\\_alloc\(\)](#), and [task\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:

**15.385.2.20 wait\_for\_event()**

```
void L4vcpu::Vcpu::wait_for_event (
    l4_utcb_t * utcb,
    l4vcpu_event_hndl_t do_event_work_cb,
    l4vcpu_setup_ipc_t setup_ipc) throw ( )    [inline]
```

Wait for event.

### Parameters


<i>utcb</i>	The UTCB to use.
<i>do_event_work_cb</i>	Call-back function that is called in case an event (such as an interrupt) is pending.
<i>setup_ipc</i>	Call-back function that is called before an IPC operation is called.

Note that event delivery remains disabled after this function returns.

Definition at line 166 of file [vcpu](#).

References [l4vcpu\\_wait\\_for\\_event\(\)](#).

Here is the call graph for this function:



The documentation for this class was generated from the following file:


- [l4/vcpu/vcpu](#)

## 15.386 L4virtio::Device Class Reference


IPC interface for virtio over [L4](#) IPC.

```
#include <l4virtio>
```

Inheritance diagram for L4virtio::Device:



Collaboration diagram for L4virtio::Device:



## Public Member Functions

- long [set\\_status](#) (unsigned status)  
*Write the VIRTIO status register.*
- long [config\\_queue](#) (unsigned queue)  
*Trigger queue configuration of the given queue.*

- long `register_ds` (`L4::lpc::Cap< L4Re::Dataspace >` ds\_cap, `l4_uint64_t` base, `l4_umword_t` offset, `l4_umword_t` size)  
*Register a shared data space with VIRTIO host.*
- long `device_config` (`L4::lpc::Out< L4::Cap< L4Re::Dataspace > >` config\_ds, `l4_addr_t` \*ds\_offset)  
*Get the dataspace with the [L4virtio](#) configuration page.*
- long `device_notification_irq` (unsigned index, `L4::lpc::Out< L4::Cap< L4::Triggerable > >` irq)  
*Get the notification interrupt corresponding to the given index.*

## Public Member Functions inherited from `L4::lcu`

- `l4_msgtag_t` `bind` (unsigned irqnum, `L4::Cap< Triggerable >` irq, `l4_utcb_t` \*utcb=`l4_utcb()`) noexcept  
*Bind an interrupt line of an interrupt controller to an interrupt object.*
- `l4_msgtag_t` `unbind` (unsigned irqnum, `L4::Cap< Triggerable >` irq, `l4_utcb_t` \*utcb=`l4_utcb()`) noexcept  
*Remove binding of an interrupt line from the interrupt controller object.*
- `l4_msgtag_t` `info` (`l4_icu_info_t` \*info, `l4_utcb_t` \*utcb=`l4_utcb()`) noexcept  
*Get information about the ICU features.*
- `l4_msgtag_t` `msi_info` (`l4_umword_t` irqnum, `l4_uint64_t` source, `l4_icu_msi_info_t` \*msi\_info)  
*Get MSI info about IRQ.*
- `l4_msgtag_t` `mask` (unsigned irqnum, `l4_umword_t` \*label=0, `l4_timeout_t` to=`L4_IPC_NEVER`, `l4_utcb_t` \*utcb=`l4_utcb()`) noexcept  
*Mask an IRQ line.*
- `l4_msgtag_t` `set_mode` (unsigned irqnum, `l4_umword_t` mode, `l4_utcb_t` \*utcb=`l4_utcb()`) noexcept  
*Set interrupt mode.*

## Public Member Functions inherited from `L4::lrq_eoi`

- `l4_msgtag_t` `unmask` (unsigned irqnum, `l4_umword_t` \*label=0, `l4_timeout_t` to=`L4_IPC_NEVER`, `l4_utcb_t` \*utcb=`l4_utcb()`) noexcept  
*Unmask the given interrupt line.*

## Additional Inherited Members

### Protected Types inherited from

`L4::Kobject_t< Device, L4::lcu, L4VIRTIO_PROTOCOL, L4::Type_info::Demand_t< 1 > >`

- typedef Device **Class**  
*The target interface type (inheriting from [Kobject\\_t](#)).*
- typedef Typeid::Iface< PROTO, Device > **\_\_iface**  
*The interface description for the derived class.*
- typedef Typeid::Merge\_list< Typeid::Iface\_list< **\_\_iface** >, typename L4::lcu::\_\_iface\_list > **\_\_iface\_list**  
*The list of all RPC interfaces provided directly or through inheritance.*

### Protected Types inherited from

`L4::Kobject_t< lcu, lrq_eoi, L4_PROTO_IRQ, Type_info::Demand_t< 1 > >`

- typedef lcu **Class**  
*The target interface type (inheriting from [Kobject\\_t](#)).*
- typedef Typeid::Iface< PROTO, lcu > **\_\_iface**  
*The interface description for the derived class.*
- typedef Typeid::Merge\_list< Typeid::Iface\_list< **\_\_iface** >, typename lrq\_eoi::\_\_iface\_list > **\_\_iface\_list**  
*The list of all RPC interfaces provided directly or through inheritance.*

**Protected Member Functions inherited from****L4::Kobject\_t< Device, L4::lcu, L4VIRTIO\_PROTOCOL, L4::Type\_info::Demand\_t< 1 > >**

- **L4::Cap< Class > c()** const noexcept

*Get the capability to ourselves.***Protected Member Functions inherited from****L4::Kobject\_t< lcu, lrcu\_eoi, L4\_PROTO\_IRQ, Type\_info::Demand\_t< 1 > >**

- **L4::Cap< Class > c()** const noexcept

*Get the capability to ourselves.***Static Protected Member Functions inherited from****L4::Kobject\_t< Device, L4::lcu, L4VIRTIO\_PROTOCOL, L4::Type\_info::Demand\_t< 1 > >**

- static void **\_\_check\_protocols\_\_()** noexcept

*Helper to check for protocol conflicts.***Static Protected Member Functions inherited from****L4::Kobject\_t< lcu, lrcu\_eoi, L4\_PROTO\_IRQ, Type\_info::Demand\_t< 1 > >**

- static void **\_\_check\_protocols\_\_()** noexcept

*Helper to check for protocol conflicts.***15.386.1 Detailed Description**

IPC interface for virtio over [L4](#) IPC.

The [L4virtio](#) protocol is an adaption of the mmio virtio transport 1.0(4). This interface allows to exchange the necessary resources: device configuration page, notification interrupts and dataspace for payload.

Notification interrupts can be configured independently for changes to the configuration space and each queue through special L4virtio-specific `notify_index` fields in the config page and queue configuration. The interface distinguishes between device-to-driver and driver-to-device notification interrupts.

Device-to-driver interrupts are configured via the ICU interface. The device announces the maximum number of supported interrupts via `lcu::info()`. The driver can then bind interrupts using `lcu::bind()`.

Driver-to-device interrupts must be requested from the device through [device\\_notification\\_irq\(\)](#).

Definition at line 39 of file [l4virtio](#).

## 15.386.2 Member Function Documentation

### 15.386.2.1 config\_queue()

```
long L4virtio::Device::config_queue (
    unsigned queue)
```

Trigger queue configuration of the given queue.

Usually all queues are configured when the status is written to running. However, in some cases queues shall be disabled or enabled dynamically, in this case this function triggers a reconfiguration from the shared memory register of the queue config.

#### Parameters

<i>queue</i>	Queue index for the queue to be configured.
--------------	---


#### Return values

0	on success.
-L4_EIO	The queue's status is invalid.
-L4_ERANGE	The queue index exceeds the number of queues.
-L4_EINVAL	Otherwise.


References [config\\_queue\(\)](#), [L4VIRTIO\\_OP\\_REGISTER\\_DS](#), and [register\\_ds\(\)](#).

Referenced by [config\\_queue\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:





### 15.386.2.2 device\_config()

```
long L4virtio::Device::device_config (
    L4::Ipc::Out< L4::Cap< L4Re::Dataspace > > config_ds,
    l4_addr_t * ds_offset)
```

Get the dataspace with the [L4virtio](#) configuration page.

#### Parameters

<i>config_ds</i>	Capability for receiving the dataspace capability for the shared L4-VIRTIO config data space.
<i>ds_offset</i>	Offset into the dataspace where the device configuration structure starts.

References [device\\_notification\\_irq\(\)](#), and [L4VIRTIO\\_OP\\_GET\\_DEVICE\\_IRQ](#).

Referenced by [register\\_ds\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 15.386.2.3 device\_notification\_irq()

```
long L4virtio::Device::device_notification_irq (
    unsigned index,
    L4::Ipc::Out< L4::Cap< L4::Triggerable > > irq)
```

Get the notification interrupt corresponding to the given index.

#### Parameters

	<i>index</i>	Index of the interrupt.
out	<i>irq</i>	Triggerable for the given index.

### Return values


<i>L4_EOK</i>	Success.
<i>L4_ENOSYS</i>	IRQ notification not supported by device.
<i>&lt;0</i>	Other error.

An index is only guaranteed to return an IRQ object when the index is set in one of the device notify index fields. The device must return the same interrupt for a given index as long as the index is in use. If an index disappears as a result of a configuration change and then is reused later, the interrupt is not guaranteed to be the same.

Interrupts must always be rerequested after a device reset.

Referenced by [device\\_config\(\)](#).

Here is the caller graph for this function:



#### 15.386.2.4 register\_ds()

```

long L4virtio::Device::register_ds (
    L4::Ipc::Cap< L4Re::Dataspace > ds_cap,
    l4_uint64_t base,
    l4_umword_t offset,
    l4_umword_t size)

```

Register a shared data space with VIRTIO host.

### Parameters

<i>ds_cap</i>	Dataspace capability to register. The lower 8 bits determine the rights mask with which the guest's rights are masked during the registration of the dataspace at the VIRTIO host.
<i>base</i>	VIRTIO guest physical start address of shared memory region
<i>offset</i>	Offset within the data space that is attached to the given <i>base</i> in the guest physical memory.
<i>size</i>	Size of the memory region in the guest


### Return values

<i>L4_EOK</i>	Operation successful.
<i>-L4_EINVAL</i>	The <code>ds_cap</code> capability is invalid, does not refer to a valid dataspace, is not a trusted dataspace if trusted dataspace validation is enabled, or <code>size</code> and <code>offset</code> specify an invalid region.
<i>-L4_ENOMEM</i>	The limit of dataspaces that can be registered has been reached or no capability slot could be allocated.
<i>-L4_ERANGE</i>	<code>offset</code> is larger than the size of the dataspace.
<i>&lt;0</i>	Any error returned by the dataspace when queried for information during setup or any error returned by the region manager from attaching the dataspace.


References [device\\_config\(\)](#), and [L4VIRTIO\\_OP\\_DEVICE\\_CONFIG](#).

Referenced by [config\\_queue\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 15.386.2.5 set\_status()

```
long L4virtio::Device::set_status (
    unsigned status)
```

Write the VIRTIO status register.

#### Parameters

<i>status</i>	Status word to write to the VIRTIO status.
---------------	--

### Return values

0	on success.
---	-------------


### Note

All other registers are accessed via shared memory.

References [L4VIRTIO\\_OP\\_CONFIG\\_QUEUE](#), and [set\\_status\(\)](#).

Referenced by [set\\_status\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



The documentation for this class was generated from the following file:


- l4/l4virtio/l4virtio

## 15.387 L4virtio::Driver::Block\_device Class Reference


Simple class for accessing a virtio block device synchronously.

```
#include <virtio-block>
```

Inheritance diagram for L4virtio::Driver::Block\_device:



Collaboration diagram for L4virtio::Driver::Block\_device:



## Data Structures

- class [Handle](#)  
*Handle to an ongoing request.*

## Public Member Functions

- void [setup\\_device](#) ([L4::Cap](#)< [L4virtio::Device](#) > srvcap, [l4\\_size\\_t](#) usermem, void \*\*userdata, [Ptr](#)< void > &user\_devaddr, [L4::Cap](#)< [L4Re::Dataspace](#) > qds=[L4::Cap](#)< [L4Re::Dataspace](#) >(), [l4\\_uint32\\_t](#) fmask0=-1U, [l4\\_uint32\\_t](#) fmask1=-1U)  
*Establish a connection to the device and set up shared memory.*
- [l4virtio\\_block\\_config\\_t](#) const & **device\_config** () const  
*Return a reference to the device configuration.*
- [Handle](#) start\_request ([l4\\_uint64\\_t](#) sector, [l4\\_uint32\\_t](#) type, Callback callback)  
*Start the setup of a new request.*
- int [add\\_block](#) ([Handle](#) handle, [Ptr](#)< void > addr, [l4\\_uint32\\_t](#) size)  
*Add a data block to a request that has already been set up.*
- int [send\\_request](#) ([Handle](#) handle)  
*Process request asynchronously.*
- int [process\\_request](#) ([Handle](#) handle)  
*Process request synchronously.*
- void [process\\_used\\_queue](#) ()  
*Process and free all items in the used queue.*

## Public Member Functions inherited from [L4virtio::Driver::Device](#)

- void [driver\\_connect](#) ([L4::Cap](#)< [L4virtio::Device](#) > srvcap, bool manage\_notify=true)  
*Contacts the device and starts the initial handshake.*
- int [bind\\_notification\\_irq](#) (unsigned index, [L4::Cap](#)< [L4::Triggerable](#) > irq) const  
*Register a triggerable to receive notifications from the device.*
- bool **fail\_state** () const  
*Return true if the device is in a fail state.*
- bool [feature\\_negotiated](#) (unsigned int feat) const  
*Check if a particular feature bit was negotiated with the device.*
- int [driver\\_acknowledge](#) ()  
*Finalize handshake with the device.*
- int [register\\_ds](#) ([L4::Cap](#)< [L4Re::Dataspace](#) > ds, [l4\\_umword\\_t](#) offset, [l4\\_umword\\_t](#) size, [l4\\_uint64\\_t](#) \*devaddr)  
*Share a dataspace with the device.*
- int [config\\_queue](#) (int num, unsigned size, [l4\\_uint64\\_t](#) desc\_addr, [l4\\_uint64\\_t](#) avail\_addr, [l4\\_uint64\\_t](#) used\_↔addr)  
*Send the virtqueue configuration to the device.*
- int [max\\_queue\\_size](#) (int num) const  
*Maximum queue size allowed by the device.*
- int [send\\_and\\_wait](#) (Virtqueue &queue, [l4\\_uint16\\_t](#) descno)  
*Send a request to the device and wait for it to be processed.*
- int [wait](#) (int index) const  
*Wait for a notification from the device.*
- int [wait\\_for\\_next\\_used](#) (Virtqueue &queue, [l4\\_uint32\\_t](#) \*len=nullptr) const  
*Wait for the next item to arrive in the used queue and return it.*
- void [send](#) (Virtqueue &queue, [l4\\_uint16\\_t](#) descno)  
*Send a request to the device.*

### 15.387.1 Detailed Description

Simple class for accessing a virtio block device synchronously.

Definition at line 36 of file [virtio-block](#).

### 15.387.2 Member Function Documentation

#### 15.387.2.1 add\_block()

```
int L4virtio::Driver::Block_device::add_block (
    Handle handle,
    Ptr< void > addr,
    l4_uint32_t size) [inline]
```

Add a data block to a request that has already been set up.

#### Parameters

<i>handle</i>	<a href="#">Handle</a> to request previously set up with <a href="#">start_request()</a> .
<i>addr</i>	Address of data block in device address space.
<i>size</i>	Size of data block.


#### Return values

<i>L4_OK</i>	Block was successfully added.
<i>-L4_EAGAIN</i>	No descriptors available. Try again later.

Definition at line 229 of file [virtio-block](#).

References [L4virtio::Virtqueue::Desc::addr](#), [L4virtio::Virtqueue::Desc::flags](#), [L4\\_EAGAIN](#), [L4\\_EOK](#), [L4virtio::Virtqueue::Desc::len](#), [L4virtio::Virtqueue::Desc::Flags::next\(\)](#), [L4virtio::Virtqueue::Desc::next](#), [L4virtio::Virtqueue::Desc::Flags::raw](#), and [L4virtio::Virtqueue::Desc::Flags::write\(\)](#).

Here is the call graph for this function:





### 15.387.2.2 process\_request()

```
int L4virtio::Driver::Block_device::process_request (
    Handle handle) [inline]
```

Process request synchronously.

#### Parameters

<i>handle</i>	Handle to request to process.
---------------	-------------------------------

#### Return values


<i>L4_EOK</i>	Request processed successfully.
<i>-L4_EAGAIN</i>	No descriptors available. Try again later.
<i>-L4_EIO</i>	IO error during request processing.
<i>-L4_ENOSYS</i>	Unsupported request.
<i>&lt;0</i>	Another unspecified error occurred.

Sends a request to the driver that was previously set up with [start\\_request\(\)](#) and [add\\_block\(\)](#) and wait for it to be executed.

Definition at line 306 of file [virtio-block](#).

References [L4virtio::Virtqueue::Desc::addr](#), [L4virtio::Virtqueue::Desc::flags](#), [L4\\_EAGAIN](#), [L4\\_EINVAL](#), [L4\\_EIO](#), [L4\\_ENOSYS](#), [L4\\_EOK](#), [L4VIRTIO\\_BLOCK\\_S\\_IOERR](#), [L4VIRTIO\\_BLOCK\\_S\\_OK](#), [L4VIRTIO\\_BLOCK\\_S\\_UNSUPP](#), [L4virtio::Virtqueue::Desc::len](#), [L4virtio::Virtqueue::Desc::Flags::next\(\)](#), [L4virtio::Virtqueue::Desc::next](#), [L4virtio::Virtqueue::Desc::Flags::write\(\)](#), [L4virtio::Driver::Device::send\\_and\\_wait\(\)](#), and [L4virtio::Virtqueue::Desc::Flags::write\(\)](#).

Here is the call graph for this function:



### 15.387.2.3 process\_used\_queue()

```
void L4virtio::Driver::Block_device::process_used_queue () [inline]
```

Process and free all items in the used queue.

If the request has a callback registered it is called after the item has been removed from the queue.

Definition at line 357 of file [virtio-block](#).

References [L4Re::chksys\(\)](#), and [L4\\_ENOSYS](#).

Here is the call graph for this function:



#### 15.387.2.4 send\_request()

```
int L4virtio::Driver::Block_device::send_request (
    Handle handle) [inline]
```

Process request asynchronously.

##### Parameters

<i>handle</i>	<a href="#">Handle</a> to request to send to the device
---------------	---

##### Return values


<i>L4_OK</i>	Request was successfully scheduled.
<i>-L4_EAGAIN</i>	No descriptors available. Try again later.

Sends a request to the driver that was previously set up with [start\\_request\(\)](#) and [add\\_block\(\)](#) and wait for it to be executed.

Definition at line 265 of file [virtio-block](#).

References [L4virtio::Virtqueue::Desc::addr](#), [L4virtio::Virtqueue::Desc::flags](#), [L4\\_EAGAIN](#), [L4\\_EOK](#), [L4virtio::Virtqueue::Desc::len](#), [L4virtio::Virtqueue::Desc::Flags::next\(\)](#), [L4virtio::Virtqueue::Desc::next](#), [L4virtio::Virtqueue::Desc::Flags::raw](#), [L4virtio::Driver::Device::send\(\)](#), and [L4virtio::Virtqueue::Desc::Flags::write\(\)](#).

Here is the call graph for this function:



## 15.387.2.5 setup\_device()

```
void L4virtio::Driver::Block_device::setup_device (
    L4::Cap< L4virtio::Device > srvcap,
    l4_size_t usermem,
    void ** userdata,
    Ptr< void > & user_devaddr,
    L4::Cap< L4Re::Dataspace > qds = L4::Cap<L4Re::Dataspace>(),
    l4_uint32_t fmask0 = -1U,
    l4_uint32_t fmask1 = -1U) [inline]
```

Establish a connection to the device and set up shared memory.

## Parameters

	<i>srvcap</i>	IPC capability of the channel to the server.
	<i>usermem</i>	Size of additional memory to share with device.
out	<i>userdata</i>	Pointer to the region of user-usable memory.
out	<i>user_devaddr</i>	Address of user-usable memory in device address space.
	<i>qds</i>	External queue dataspace. If this capability is invalid, the function will attempt to allocate a dataspace on its own. Note that the external queue dataspace must be large enough.
	<i>fmask0</i>	Feature bits 0..31 that the driver supports.
	<i>fmask1</i>	Feature bits 32..63 that the driver supports.

This function starts a handshake with the device and sets up the virtqueues for communication and the additional data structures for the block device. It will also allocate and share additional memory that the caller then can use freely, i.e. normally this memory would be used as a reception buffer. The caller may also decide to not make use of this convenience function and request 0 bytes in *usermem*. Then it has to allocate the block buffers for sending/receiving payload manually and share them using [register\\_ds\(\)](#).

Definition at line 92 of file [virtio-block](#).

References [L4Re::chkcap\(\)](#), [L4Re::chksys\(\)](#), [L4virtio::Driver::Device::config\\_queue\(\)](#), [L4Re::Mem\\_alloc::Continuous](#), [L4virtio::Driver::Device::driver\\_acknowledge\(\)](#), [L4virtio::Driver::Device::driver\\_connect\(\)](#), [L4Re::Env::env\(\)](#), [L4\\_EINVAL](#), [L4\\_ENODEV](#), [L4\\_PAGESHIFT](#), [l4\\_round\\_page\(\)](#), [l4\\_round\\_size\(\)](#), [L4VIRTIO\\_ID\\_BLOCK](#), [L4::lpc::make\\_cap\\_rw\(\)](#), [L4Re::Util::make\\_unique\\_cap\(\)](#), [L4virtio::Driver::Device::max\\_queue\\_size\(\)](#), [L4Re::Mem\\_alloc::Pinned](#), [L4virtio::Driver::Device::register\\_ds\(\)](#), [L4Re::Rm::F::RW](#), and [L4Re::Rm::F::Search\\_addr](#).




## 15.388 L4virtio::Driver::Block\_device::Handle Class Reference

[Handle](#) to an ongoing request.

```
#include <virtio-block>
```

Collaboration diagram for L4virtio::Driver::Block\_device::Handle:



### 15.388.1 Detailed Description

[Handle](#) to an ongoing request.

Definition at line 56 of file [virtio-block](#).

The documentation for this class was generated from the following file:


- l4/l4virtio/client/virtio-block

## 15.389 L4virtio::Driver::Device Class Reference


Client-side implementation for a general virtio device.

```
#include <l4virtio>
```

Inheritance diagram for L4virtio::Driver::Device:



Collaboration diagram for L4virtio::Driver::Device:



## Public Member Functions

- void `driver_connect` (`L4::Cap< L4virtio::Device >` `src`, `bool manage_notify=true`)  
Contacts the device and starts the initial handshake.
- int `bind_notification_irq` (unsigned index, `L4::Cap< L4::Triggerable >` `irq`) const  
Register a triggerable to receive notifications from the device.
- bool `fail_state` () const

- Return true if the device is in a fail state.*

  - bool `feature_negotiated` (unsigned int feat) const

*Check if a particular feature bit was negotiated with the device.*
- int `driver_acknowledge` ()

*Finalize handshake with the device.*
- int `register_ds` (L4::Cap< L4Re::Dataspace > ds, l4\_umword\_t offset, l4\_umword\_t size, l4\_uint64\_t \*devaddr)

*Share a dataspace with the device.*
- int `config_queue` (int num, unsigned size, l4\_uint64\_t desc\_addr, l4\_uint64\_t avail\_addr, l4\_uint64\_t used\_addr)

*Send the virtqueue configuration to the device.*
- int `max_queue_size` (int num) const

*Maximum queue size allowed by the device.*
- int `send_and_wait` (Virtqueue &queue, l4\_uint16\_t descno)

*Send a request to the device and wait for it to be processed.*
- int `wait` (int index) const

*Wait for a notification from the device.*
- int `wait_for_next_used` (Virtqueue &queue, l4\_uint32\_t \*len=NULLPTR) const

*Wait for the next item to arrive in the used queue and return it.*
- void `send` (Virtqueue &queue, l4\_uint16\_t descno)

*Send a request to the device.*

## 15.389.1 Detailed Description

Client-side implementation for a general virtio device.

Definition at line 31 of file `l4virtio`.

## 15.389.2 Member Function Documentation

### 15.389.2.1 bind\_notification\_irq()

```
int L4virtio::Driver::Device::bind_notification_irq (
    unsigned index,
    L4::Cap< L4::Triggerable > irq) const [inline]
```

Register a triggerable to receive notifications from the device.

#### Parameters


	<i>index</i>	Index of the interrupt.
out	<i>irq</i>	Triggerable to register for notifications.

Definition at line 129 of file `l4virtio`.

References `l4_error()`.



Here is the call graph for this function:



### 15.389.2.2 config\_queue()

```
int L4virtio::Driver::Device::config_queue (
    int num,
    unsigned size,
    l4_uint64_t desc_addr,
    l4_uint64_t avail_addr,
    l4_uint64_t used_addr) [inline]
```

Send the virtqueue configuration to the device.


#### Parameters

<i>num</i>	Number of queue to configure.
<i>size</i>	Size of rings in the queue, must be a power of 2)
<i>desc_addr</i>	Address of descriptor table (device address)
<i>avail_addr</i>	Address of available ring (device address)
<i>used_addr</i>	Address of used ring (device address)

Definition at line 212 of file [l4virtio](#).

Referenced by [L4virtio::Driver::Block\\_device::setup\\_device\(\)](#), and [L4virtio::Driver::Virtio\\_net\\_device::setup\\_device\(\)](#).

Here is the caller graph for this function:



### 15.389.2.3 driver\_acknowledge()

```
int L4virtio::Driver::Device::driver_acknowledge () [inline]
```

Finalize handshake with the device.


Must be called after all queues have been set up and before the first request is sent. It is still possible to add more shared dataspace after the handshake has been finished.

Definition at line 156 of file [l4virtio](#).


References [L4Re::chksys\(\)](#), [L4\\_EINVAL](#), [L4\\_EIO](#), [L4\\_ENODEV](#), [L4\\_EOK](#), [L4VIRTIO\\_FEATURE\\_VERSION\\_1](#), [l4virtio\\_get\\_feature\(\)](#), [L4VIRTIO\\_STATUS\\_DRIVER\\_OK](#), and [L4VIRTIO\\_STATUS\\_FEATURES\\_OK](#).

Referenced by [L4virtio::Driver::Block\\_device::setup\\_device\(\)](#), and [L4virtio::Driver::Virtio\\_net\\_device::setup\\_device\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 15.389.2.4 driver\_connect()

```
void L4virtio::Driver::Device::driver_connect (
    L4::Cap< L4virtio::Device > srvcap,
    bool manage_notify = true) [inline]
```

Contacts the device and starts the initial handshake.

### Parameters

<i>svrcap</i>	Capability for device communication.
<i>manage_notify</i>	Set up a semaphore for notifications from the device. See below.

### Exceptions

<a href="#">L4::Runtime_error</a>	if the initialisation fails
-----------------------------------	-----------------------------

This function contacts the server, sets up the notification channels and the configuration dataspace. After this is done, the caller can set up any dataspaces it needs. The initialisation then needs to be finished by calling [driver\\_acknowledge\(\)](#).

Per default this function creates and registers a semaphore for receiving notification from the device. This semaphore is used in the blocking functions [send\\_and\\_wait\(\)](#), [wait\(\)](#) and [next\\_used\(\)](#).


When `manage_notify` is false, then the caller may manually register and handle notification interrupts from the device. This is for example useful, when the client runs in an application with a server loop.

Definition at line 56 of file [l4virtio](#).


References [L4Re::chkcap\(\)](#), [L4Re::chksys\(\)](#), [L4Re::Env::env\(\)](#), [L4\\_EINVAL](#), [L4\\_EIO](#), [L4\\_ENODEV](#), [l4\\_error\(\)](#), [L4\\_PAGEMASK](#), [L4\\_PAGESHIFT](#), [L4\\_PAGESIZE](#), [L4\\_SUPERPAGESIZE](#), [L4VIRTIO\\_STATUS\\_ACKNOWLEDGE](#), [L4VIRTIO\\_STATUS\\_DRIVER](#), [L4::lpc::make\\_cap\\_rw\(\)](#), [L4Re::Util::make\\_unique\\_cap\(\)](#), [L4Re::Rm::F::RW](#), and [L4Re::Rm::F::Search\\_addr](#).

Referenced by [L4virtio::Driver::Block\\_device::setup\\_device\(\)](#), and [L4virtio::Driver::Virtio\\_net\\_device::setup\\_device\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 15.389.2.5 feature\_negotiated()

```
bool L4virtio::Driver::Device::feature_negotiated (
    unsigned int feat) const [inline]
```

Check if a particular feature bit was negotiated with the device.

The result is only valid after [driver\\_acknowledge\(\)](#) was called (when the handshake with the device was completed).

#### Parameters

<i>feat</i>	The feature bit.
-------------	------------------


#### Return values

<i>true</i>	The feature is supported by both driver and device.
<i>false</i>	The feature is not supported by the driver and/or device.

Definition at line [145](#) of file [l4virtio](#).

References [l4virtio\\_get\\_feature\(\)](#).

Here is the call graph for this function:



### 15.389.2.6 max\_queue\_size()

```
int L4virtio::Driver::Device::max_queue_size (
    int num) const [inline]
```

Maximum queue size allowed by the device.


#### Parameters

<i>num</i>	Number of queue for which to determine the maximum size.
------------	--

Definition at line 230 of file [l4virtio](#).

Referenced by [L4virtio::Driver::Virtio\\_net\\_device::rx\\_queue\\_size\(\)](#), [L4virtio::Driver::Block\\_device::setup\\_device\(\)](#), and [L4virtio::Driver::Virtio\\_net\\_device::tx\\_queue\\_size\(\)](#).

Here is the caller graph for this function:



### 15.389.2.7 register\_ds()

```
int L4virtio::Driver::Device::register_ds (
    L4::Cap< L4Re::Dataspace > ds,
    l4_umword_t offset,
    l4_umword_t size,
    l4_uint64_t * devaddr) [inline]
```

Share a dataspace with the device.

#### Parameters

<i>ds</i>	Dataspace to share with the device.
<i>offset</i>	Offset in dataspace where the shared part starts.
<i>size</i>	Total size in bytes of the shared space.
<i>devaddr</i>	Start of shared space in the device address space.

Although this function allows to share only a part of the given dataspace for convenience, the granularity of sharing is always the dataspace level. Thus, the remainder of the dataspace is not protected from the device.

When communicating with the device, addresses must be given with respect to the device address space. This is not the same as the virtual address space of the client in order to not leak information about the address space layout.

Definition at line 196 of file [l4virtio](#).


References [L4::lpc::make\\_cap\\_rw\(\)](#).

Referenced by [L4virtio::Driver::Block\\_device::setup\\_device\(\)](#), and [L4virtio::Driver::Virtio\\_net\\_device::setup\\_device\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



#### 15.389.2.8 send()

```
void L4virtio::Driver::Device::send (
    Virtqueue & queue,
    l4_uint16_t descno) [inline]
```

Send a request to the device.

##### Parameters

<i>queue</i>	Queue that contains the request in its descriptor table
<i>descno</i>	Index of first entry in descriptor table where

Definition at line 312 of file [l4virtio](#).


References [L4virtio::Driver::Virtqueue::enqueue\\_descriptor\(\)](#).

Referenced by [send\\_and\\_wait\(\)](#), [L4virtio::Driver::Block\\_device::send\\_request\(\)](#), and [L4virtio::Driver::Virtio\\_net\\_device::tx\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 15.389.2.9 send\_and\_wait()

```
int L4virtio::Driver::Device::send_and_wait (
    Virtqueue & queue,
    l4_uint16_t descno) [inline]
```

Send a request to the device and wait for it to be processed.

#### Parameters

<i>queue</i>	Queue that contains the request in its descriptor table
<i>descno</i>	Index of first entry in descriptor table where

This function provides a simple mechanism to send requests synchronously. It must not be used with other requests at the same time as it directly waits for a notification on the device irq cap.

**Precondition**


`driver_connect()` was called with `manage_notify`.

Definition at line 247 of file `l4virtio`.

References `L4_EINVAL`, `L4_EOK`, `send()`, and `wait_for_next_used()`.

Referenced by `L4virtio::Driver::Block_device::process_request()`.

Here is the call graph for this function:



Here is the caller graph for this function:

**15.389.2.10 wait()**

```
int L4virtio::Driver::Device::wait (
    int index) const [inline]
```

Wait for a notification from the device.

**Parameters**

<i>index</i>	Notification slot to wait for.
--------------	--------------------------------



**Precondition**


[driver\\_connect\(\)](#) was called with `manage_notify`.

Definition at line 268 of file [l4virtio](#).

References [L4\\_EEXIST](#), [l4\\_ipc\\_error\(\)](#), and [l4\\_utcb\(\)](#).

Referenced by [wait\\_for\\_next\\_used\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:

**15.389.2.11 wait\_for\_next\_used()**

```

int L4virtio::Driver::Device::wait_for_next_used (
    Virtqueue & queue,
    l4_uint32_t * len = nullptr) const [inline]
  
```

Wait for the next item to arrive in the used queue and return it.

**Parameters**

	<i>queue</i>	A queue.
out	<i>len</i>	(optional) Size of valid data in finished block. Note that this is the value reported by the device, which may set it to a value that is larger than the original buffer size.

**Return values**

$\geq 0$	Descriptor number of item removed from used queue.
$< 0$	IPC error while waiting for notification.

The call blocks until the next item is available in the used queue.

**Precondition**


`driver_connect()` was called with `manage_notify`.

Definition at line 291 of file `l4virtio`.


References `L4virtio::Driver::Virtqueue::find_next_used()`, and `wait()`.

Referenced by `send_and_wait()`.

Here is the call graph for this function:



Here is the caller graph for this function:



The documentation for this class was generated from the following file:


- `I4/I4virtio/client/I4virtio`

## 15.390 L4virtio::Driver::Virtio\_net\_device Class Reference


Simple class for accessing a virtio net device.

```
#include <virtio-net>
```

Inheritance diagram for L4virtio::Driver::Virtio\_net\_device:



Collaboration diagram for L4virtio::Driver::Virtio\_net\_device:



## Data Structures

- struct [Packet](#)

Structure for a network packet (header including data) with maximum size, assuming that no extra features have been negotiated.

## Public Member Functions

- int [rx\\_queue\\_size](#) () const  
*Return the maximum receive queue size allowed by the device.*
- int [tx\\_queue\\_size](#) () const  
*Return the maximum transmit queue size allowed by the device.*
- void [setup\\_device](#) (L4::Cap< L4virtio::Device > srvcap, L4::Cap< L4Re::Dataspace > queue\_ds=L4::Cap< L4Re::Dataspace >::Invalid)  
*Establish a connection to the device and set up shared memory.*
- [l4virtio\\_net\\_config\\_t](#) const & [device\\_config](#) () const  
*Return a reference to the device configuration.*
- int [bind\\_rx\\_notification\\_irq](#) (L4::Cap< L4::Thread > thread, [l4\\_umword\\_t](#) label)  
*Bind the rx notification IRQ to the specified thread.*
- [Packet](#) & [rx\\_pkt](#) ([l4\\_uint16\\_t](#) descno)  
*Return a reference to the RX packet buffer of the specified descriptor, e.g.*
- [l4\\_uint16\\_t](#) [wait\\_rx](#) ([l4\\_uint32\\_t](#) \*len=nullptr)  
*Block until a network packet has been received from the device and return the descriptor number.*
- void [finish\\_rx](#) ([l4\\_uint16\\_t](#) descno)  
*Free an RX descriptor number to make it available for the RX queue again.*
- void [queue\\_rx](#) ()  
*Queue new available descriptors in the RX queue.*
- bool [tx](#) (std::function< [l4\\_uint32\\_t](#)([Packet](#) &)> prepare)  
*Attempt to allocate a descriptor in the TX queue and transmit the packet, after calling the prepare callback.*

## Public Member Functions inherited from [L4virtio::Driver::Device](#)

- void [driver\\_connect](#) (L4::Cap< L4virtio::Device > srvcap, bool manage\_notify=true)  
*Contacts the device and starts the initial handshake.*
- int [bind\\_notification\\_irq](#) (unsigned index, L4::Cap< L4::Triggerable > irq) const  
*Register a triggerable to receive notifications from the device.*
- bool [fail\\_state](#) () const  
*Return true if the device is in a fail state.*
- bool [feature\\_negotiated](#) (unsigned int feat) const  
*Check if a particular feature bit was negotiated with the device.*
- int [driver\\_acknowledge](#) ()  
*Finalize handshake with the device.*
- int [register\\_ds](#) (L4::Cap< L4Re::Dataspace > ds, [l4\\_umword\\_t](#) offset, [l4\\_umword\\_t](#) size, [l4\\_uint64\\_t](#) \*devaddr)  
*Share a dataspace with the device.*
- int [config\\_queue](#) (int num, unsigned size, [l4\\_uint64\\_t](#) desc\_addr, [l4\\_uint64\\_t](#) avail\_addr, [l4\\_uint64\\_t](#) used\_↵ addr)  
*Send the virtqueue configuration to the device.*
- int [max\\_queue\\_size](#) (int num) const  
*Maximum queue size allowed by the device.*
- int [send\\_and\\_wait](#) (Virtqueue &queue, [l4\\_uint16\\_t](#) descno)  
*Send a request to the device and wait for it to be processed.*
- int [wait](#) (int index) const  
*Wait for a notification from the device.*
- int [wait\\_for\\_next\\_used](#) (Virtqueue &queue, [l4\\_uint32\\_t](#) \*len=nullptr) const  
*Wait for the next item to arrive in the used queue and return it.*
- void [send](#) (Virtqueue &queue, [l4\\_uint16\\_t](#) descno)  
*Send a request to the device.*

### 15.390.1 Detailed Description

Simple class for accessing a virtio net device.

Definition at line 30 of file [virtio-net](#).

### 15.390.2 Member Function Documentation

#### 15.390.2.1 `bind_rx_notification_irq()`

```
int L4virtio::Driver::Virtio_net_device::bind_rx_notification_irq (
    L4::Cap< L4::Thread > thread,
    l4_umword_t label) [inline]
```

Bind the rx notification IRQ to the specified thread.


##### Parameters

<i>thread</i>	Thread to bind the notification IRQ to.
<i>label</i>	Label to assign to the IRQ.

Definition at line 181 of file [virtio-net](#).

References [l4\\_error\(\)](#).

Here is the call graph for this function:



#### 15.390.2.2 `finish_rx()`

```
void L4virtio::Driver::Virtio_net_device::finish_rx (
    l4_uint16_t descno) [inline]
```

Free an RX descriptor number to make it available for the RX queue again.

##### Parameters

<i>descno</i>	Descriptor number in the virtio queue.
---------------	--

Usually [queue\\_rx\(\)](#) should be called afterwards to queue the freed descriptor(s).

Definition at line 242 of file [virtio-net](#).

### 15.390.2.3 rx\_pkt()

```
Packet & L4virtio::Driver::Virtio_net_device::rx_pkt (
    l4_uint16_t descno) [inline]
```

Return a reference to the RX packet buffer of the specified descriptor, e.g.

from [wait\\_rx\(\)](#).

#### Parameters

<i>descno</i>	Descriptor number in the virtio queue.
---------------	--

Definition at line 192 of file [virtio-net](#).

### 15.390.2.4 rx\_queue\_size()

```
int L4virtio::Driver::Virtio_net_device::rx_queue_size () const [inline]
```

Return the maximum receive queue size allowed by the device.


[wait\\_rx\(\)](#) will return a descriptor number that is smaller than this size.

Definition at line 47 of file [virtio-net](#).


References [L4virtio::Driver::Device::max\\_queue\\_size\(\)](#).

Referenced by [setup\\_device\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 15.390.2.5 setup\_device()

```
void L4virtio::Driver::Virtio_net_device::setup_device (
    L4::Cap< L4virtio::Device > srvcap,
    L4::Cap< L4Re::Dataspace > queue_ds = L4::Cap<L4Re::Dataspace>::Invalid) [inline]
```

Establish a connection to the device and set up shared memory.

#### Parameters


<i>srvcap</i>	IPC capability of the channel to the server.
<i>queue_ds</i>	(optional) External queue dataspace. If this capability is invalid, the function will attempt to allocate a dataspace on its own. Note that the external queue dataspace must be large enough.

This function starts a handshake with the device and sets up the virtqueues for communication and the additional data structures for the network device.

Definition at line 70 of file [virtio-net](#).

References [L4Re::chkcap\(\)](#), [L4Re::chksys\(\)](#), [L4virtio::Driver::Device::config\\_queue\(\)](#), [L4Re::Mem\\_alloc::Continuous](#), [L4virtio::Driver::Device::driver\\_acknowledge\(\)](#), [L4virtio::Driver::Device::driver\\_connect\(\)](#), [L4Re::Env::env\(\)](#), [L4::Cap\\_base::Invalid](#), [L4\\_EINVAL](#), [L4\\_ENODEV](#), [I4\\_error\(\)](#), [L4\\_PAGESHIFT](#), [I4\\_round\\_size\(\)](#), [L4VIRTIO\\_FEATURE\\_VERSION\\_1](#), [L4VIRTIO\\_ID\\_NET](#), [I4virtio\\_set\\_feature\(\)](#), [L4::lpc::make\\_cap\\_rw\(\)](#), [L4Re::Util::make\\_unique\\_cap\(\)](#), [L4Re::Mem\\_alloc::Pinned](#), [L4virtio::Driver::Device::register\\_ds\(\)](#), [L4Re::Rm::F::RW](#), [rx\\_queue\\_size\(\)](#), [L4Re::Rm::F::Search\\_addr](#), and [tx\\_queue\\_size\(\)](#).

Here is the call graph for this function:





### 15.390.2.6 tx()

```
bool L4virtio::Driver::Virtio_net_device::tx (
    std::function< 14_uint32_t(Packet &)> prepare) [inline]
```

Attempt to allocate a descriptor in the TX queue and transmit the packet, after calling the prepare callback.

#### Parameters

<i>prepare</i>	Function that fills the packet with data, should return the length of the data copied to the packet.
----------------	--

#### Return values


<i>true</i>	The packet was queued.
<i>false</i>	TX queue is full.

The prepare callback should fill the packet with data and return the length of the packet data (without the size of the virtio-net packet header).

Definition at line 272 of file [virtio-net](#).

References [L4virtio::Driver::Device::send\(\)](#).

Here is the call graph for this function:



### 15.390.2.7 tx\_queue\_size()

```
int L4virtio::Driver::Virtio_net_device::tx_queue_size () const [inline]
```

Return the maximum transmit queue size allowed by the device.


[tx\(\)](#) will fail if the amount of queued packets exceeds this size.

Definition at line 54 of file [virtio-net](#).


References [L4virtio::Driver::Device::max\\_queue\\_size\(\)](#).

Referenced by [setup\\_device\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 15.390.2.8 wait\_rx()

```
l4_uint16_t L4virtio::Driver::Virtio_net_device::wait_rx (
    l4_uint32_t * len = nullptr) [inline]
```

Block until a network packet has been received from the device and return the descriptor number.

#### Precondition

The calling thread must be bound to the rx notification IRQ via `bind_rx_notification_irq()`.

#### Parameters

out	len	(optional) Length of valid data in RX packet.
-----	-----	---

#### Returns

Descriptor number of received packet.

The packet data can be obtained with `rx_pkt()`. `finish_rx()` should be called after the packet buffer can be returned to the RX queue.

Definition at line 214 of file `virtio-net`.

References `L4Re::chksys()`.

Here is the call graph for this function:



The documentation for this class was generated from the following file:


- l4/l4virtio/client/virtio-net

## 15.391 L4virtio::Driver::Virtio\_net\_device::Packet Struct Reference

Structure for a network packet (header including data) with maximum size, assuming that no extra features have been negotiated.

```
#include <virtio-net>
```

Collaboration diagram for L4virtio::Driver::Virtio\_net\_device::Packet:



### 15.391.1 Detailed Description

Structure for a network packet (header including data) with maximum size, assuming that no extra features have been negotiated.

Definition at line 37 of file [virtio-net](#).

The documentation for this struct was generated from the following file:


- l4/l4virtio/client/virtio-net

## 15.392 L4virtio::Driver::Virtqueue Class Reference


Driver-side implementation of a [Virtqueue](#).

```
#include <virtqueue>
```

Inheritance diagram for L4virtio::Driver::Virtqueue:



Collaboration diagram for L4virtio::Driver::Virtqueue:



## Public Member Functions

- void `initialize_rings` (unsigned `num`)  
Initialize the descriptor table and the index structures of this queue.
- void `init_queue` (unsigned `num`, void `*desc`, void `*avail`, void `*used`)  
Initialize this virtqueue.
- void `init_queue` (unsigned `num`, void `*base`)

- Initialize this virtqueue.*
  - [l4\\_uint16\\_t alloc\\_descriptor](#) ()
    - Allocate and return an unused descriptor from the descriptor table.*
  - void [enqueue\\_descriptor](#) ([l4\\_uint16\\_t](#) descno)
    - Enqueue a descriptor in the available ring.*
  - [Desc & desc](#) ([l4\\_uint16\\_t](#) descno)
    - Return a reference to a descriptor in the descriptor table.*
  - [l4\\_uint16\\_t find\\_next\\_used](#) ([l4\\_uint32\\_t](#) \*len=NULLptr)
    - Return the next finished block.*
  - void [free\\_descriptor](#) ([l4\\_uint16\\_t](#) head, [l4\\_uint16\\_t](#) tail)
    - Free a chained list of descriptors in the descriptor queue.*

## Public Member Functions inherited from [L4virtio::Virtqueue](#)

- void [disable](#) ()
  - Completely disable the queue.*
- unsigned long [total\\_size](#) () const
  - Calculate the total size of this virtqueue.*
- unsigned long [avail\\_offset](#) () const
  - Get the offset of the available ring from the descriptor table.*
- unsigned long [used\\_offset](#) () const
  - Get the offset of the used ring from the descriptor table.*
- void [setup](#) (unsigned [num](#), void \*desc, void \*avail, void \*used)
  - Enable this queue.*
- void [setup\\_simple](#) (unsigned [num](#), void \*ring)
  - Enable this queue.*
- void [dump](#) ([Desc](#) const \*d) const
  - Dump descriptors for this queue.*
- bool [ready](#) () const
  - Test if this queue is in working state.*
- unsigned [num](#) () const
- bool [no\\_notify\\_guest](#) () const
  - Get the no IRQ flag of this queue.*
- bool [no\\_notify\\_host](#) () const
  - Get the no notify flag of this queue.*
- void [no\\_notify\\_host](#) (bool value)
  - Set the no-notify flag for this queue.*
- [l4\\_uint16\\_t](#) [get\\_avail\\_idx](#) () const
  - Get available index from available ring (for debugging).*
- [l4\\_uint16\\_t](#) [get\\_tail\\_avail\\_idx](#) () const
  - Get tail-available index stored in local state (for debugging).*

## Additional Inherited Members

## Public Types inherited from [L4virtio::Virtqueue](#)

- enum
  - Fixed alignment values for different parts of a virtqueue.*

## Static Public Member Functions inherited from L4virtio::Virtqueue

- static unsigned long [total\\_size](#) (unsigned [num](#))  
*Calculate the total size for a virtqueue of the given dimensions.*
- static unsigned long [desc\\_size](#) (unsigned [num](#))  
*Calculate the size of the descriptor table for [num](#) entries.*
- static unsigned long [desc\\_align](#) ()  
*Get the alignment in zero LSBs needed for the descriptor table.*
- static unsigned long [avail\\_size](#) (unsigned [num](#))  
*Calculate the size of the available ring for [num](#) entries.*
- static unsigned long [avail\\_align](#) ()  
*Get the alignment in zero LSBs needed for the available ring.*
- static unsigned long [used\\_size](#) (unsigned [num](#))  
*Calculate the size of the used ring for [num](#) entries.*
- static unsigned long [used\\_align](#) ()  
*Get the alignment in zero LSBs needed for the used ring.*

## Protected Member Functions inherited from L4virtio::Virtqueue

- [Virtqueue](#) ()=default  
*Create a disabled virtqueue.*

## Protected Attributes inherited from L4virtio::Virtqueue

- [Desc](#) \* [\\_desc](#) = nullptr  
*pointer to descriptor table, NULL if queue is off.*
- [Avail](#) \* [\\_avail](#) = nullptr  
*pointer to available ring.*
- [Used](#) \* [\\_used](#) = nullptr  
*pointer to used ring.*
- [l4\\_uint16\\_t](#) [\\_current\\_avail](#) = 0  
*The life counter for the queue.*
- [l4\\_uint16\\_t](#) [\\_idx\\_mask](#) = 0  
*mask used for indexing into the descriptor table and the rings.*

### 15.392.1 Detailed Description

Driver-side implementation of a [Virtqueue](#).

Adds function for managing the descriptor list, enqueueing new and dequeueing finished requests.

#### Note

The [Virtqueue](#) implementation is not thread-safe.

Definition at line 470 of file [virtqueue](#).

## 15.392.2 Member Function Documentation

### 15.392.2.1 alloc\_descriptor()

```
l4_uint16_t L4virtio::Driver::Virtqueue::alloc_descriptor () [inline]
```

Allocate and return an unused descriptor from the descriptor table.

The descriptor will be removed from the free list, the content should be considered undefined. After use, it needs to be freed using [free\\_descriptor\(\)](#).

#### Returns

The index of the reserved descriptor or Virtqueue::Eoq if no free descriptor is available.

Note: the implementation uses  $(2^{16} - 1)$  as the end of queue marker. That means that the final entry in the queue can not be allocated iff the queue size is  $2^{16}$ .

Definition at line 558 of file [virtqueue](#).

References [L4virtio::Virtqueue::\\_desc](#).

### 15.392.2.2 desc()

```
Desc & L4virtio::Driver::Virtqueue::desc (
    l4_uint16_t descno) [inline]
```

Return a reference to a descriptor in the descriptor table.

#### Parameters


<i>descno</i>	Index of the descriptor, expected to be in correct range.
---------------	---

Definition at line 590 of file [virtqueue](#).

References [L4virtio::Virtqueue::\\_desc](#), and [L4virtio::Virtqueue::\\_idx\\_mask](#).

Referenced by [init\\_queue\(\)](#).

Here is the caller graph for this function:





### 15.392.2.3 enqueue\_descriptor()

```
void L4virtio::Driver::Virtqueue::enqueue_descriptor (
    14_uint16_t descno) [inline]
```

Enqueue a descriptor in the available ring.

#### Parameters


<i>descno</i>	Index of the head descriptor to enqueue.
---------------	--

Definition at line 574 of file [virtqueue](#).

References [L4virtio::Virtqueue::\\_avail](#), and [L4virtio::Virtqueue::\\_idx\\_mask](#).

Referenced by [L4virtio::Driver::Device::send\(\)](#).

Here is the caller graph for this function:



### 15.392.2.4 find\_next\_used()

```
14_uint16_t L4virtio::Driver::Virtqueue::find_next_used (
    14_uint32_t * len = nullptr) [inline]
```

Return the next finished block.

#### Parameters

<i>out</i>	<i>len</i>	(optional) Size of valid data in finished block. Note that this is the value reported by the device, which may set it to a value that is larger than the original buffer size.
------------	------------	--

#### Returns

Index of the head or Virtqueue::Eoq if no used element is currently available.

Definition at line 609 of file [virtqueue](#).

References [L4virtio::Virtqueue::\\_current\\_avail](#), [L4virtio::Virtqueue::\\_idx\\_mask](#), and [L4virtio::Virtqueue::\\_used](#).

Referenced by [L4virtio::Driver::Device::wait\\_for\\_next\\_used\(\)](#).

Here is the caller graph for this function:



### 15.392.2.5 free\_descriptor()

```
void L4virtio::Driver::Virtqueue::free_descriptor (
    l4_uint16_t head,
    l4_uint16_t tail) [inline]
```

Free a chained list of descriptors in the descriptor queue.

#### Parameters

<i>head</i>	Index of the first element in the descriptor chain.
<i>tail</i>	Index of the last element in the descriptor chain.

Simply takes the descriptor chain and prepends it to the beginning of the free list. Assumes that the list has been correctly chained.

Definition at line 631 of file [virtqueue](#).

References [L4virtio::Virtqueue::\\_desc](#), and [L4virtio::Virtqueue::\\_idx\\_mask](#).

### 15.392.2.6 init\_queue() [1/2]

```
void L4virtio::Driver::Virtqueue::init_queue (
    unsigned num,
    void * base) [inline]
```

Initialize this virtqueue.

#### Parameters


<i>num</i>	The number of entries in the descriptor table, the available ring, and the used ring (must be a power of 2).
<i>base</i>	The base address for the queue data structure.

This function sets up the memory and initializes the freelist.

Definition at line 537 of file [virtqueue](#).

References [initialize\\_rings\(\)](#), [L4virtio::Virtqueue::num\(\)](#), and [L4virtio::Virtqueue::setup\\_simple\(\)](#).

Here is the call graph for this function:



### 15.392.2.7 init\_queue() [2/2]

```
void L4virtio::Driver::Virtqueue::init_queue (
    unsigned num,
    void * desc,
    void * avail,
    void * used) [inline]
```

Initialize this virtqueue.

#### Parameters


<i>num</i>	The number of entries in the descriptor table, the available ring, and the used ring (must be a power of 2).
<i>desc</i>	The address of the descriptor table. (Must be Desc_align aligned and at least desc_size(num) bytes in size.)
<i>avail</i>	The address of the available ring. (Must be Avail_align aligned and at least avail_size(num) bytes in size.)
<i>used</i>	The address of the used ring. (Must be Used_align aligned and at least used_size(num) bytes in size.)

This function sets up the memory and initializes the freelist.

Definition at line 522 of file [virtqueue](#).

References [desc\(\)](#), [initialize\\_rings\(\)](#), [L4virtio::Virtqueue::num\(\)](#), and [L4virtio::Virtqueue::setup\(\)](#).

Here is the call graph for this function:



### 15.392.2.8 initialize\_rings()

```
void L4virtio::Driver::Virtqueue::initialize_rings (
    unsigned num) [inline]
```

Initialize the descriptor table and the index structures of this queue.

## Parameters

<i>num</i>	The number of entries in the descriptor table, the available ring, and the used ring (must be a power of 2).
------------	--

## Precondition


The queue must be set up correctly with [setup\(\)](#) or [setup\\_simple\(\)](#).

Definition at line [494](#) of file [virtqueue](#).


References [L4virtio::Virtqueue::\\_avail](#), [L4virtio::Virtqueue::\\_desc](#), [L4virtio::Virtqueue::\\_used](#), and [L4virtio::Virtqueue::num\(\)](#).

Referenced by [init\\_queue\(\)](#), and [init\\_queue\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



The documentation for this class was generated from the following file:


- `I4/I4virtio/virtqueue`

## 15.393 L4virtio::Ptr< T > Class Template Reference


Pointer used in virtio descriptors.

```
#include <virtqueue>
```

Inheritance diagram for L4virtio::Ptr< T >:



Collaboration diagram for L4virtio::Ptr< T >:



## Public Types

- enum [Invalid\\_type](#) { [Invalid](#) }  
Type for making an invalid (NULL) [Ptr](#).

## Public Member Functions

- [Ptr](#) ([Invalid\\_type](#))  
Make and invalid [Ptr](#).
- [Ptr](#) ([l4\\_uint64\\_t](#) vm\_addr)  
Make a [Ptr](#) from a raw 64bit address.
- [l4\\_uint64\\_t](#) get () const
- bool [is\\_valid](#) () const

### 15.393.1 Detailed Description

```
template<typename T>
class L4virtio::Ptr< T >
```

Pointer used in virtio descriptors.

As the descriptor contain guest addresses these pointers cannot be dereferenced directly.

Definition at line 47 of file [virtqueue](#).

### 15.393.2 Member Enumeration Documentation

#### 15.393.2.1 Invalid\_type

```
template<typename T>
enum L4virtio::Ptr::Invalid_type
```

Type for making an invalid (NULL) [Ptr](#).

#### Enumerator

Invalid	Use to set a <a href="#">Ptr</a> to invalid (NULL).
---------	---

Definition at line 51 of file [virtqueue](#).

### 15.393.3 Member Function Documentation

#### 15.393.3.1 get()

```
template<typename T>
l4_uint64_t L4virtio::Ptr< T >::get () const [inline]
```


##### Returns

The raw 64bit address of the stored pointer.

Definition at line 62 of file [virtqueue](#).

Referenced by [L4virtio::Svr::Driver\\_mem\\_list\\_t< No\\_custom\\_data >::load\\_desc\(\)](#), [L4virtio::Svr::Driver\\_mem\\_list\\_t< No\\_custom\\_data >::load\\_desc\(\)](#), [L4virtio::Svr::Driver\\_mem\\_list\\_t< No\\_custom\\_data >::load\\_desc\(\)](#), and [L4virtio::Svr::Driver\\_mem\\_region\\_t< No\\_custom\\_data >::local](#).

Here is the caller graph for this function:



#### 15.393.3.2 is\_valid()

```
template<typename T>
bool L4virtio::Ptr< T >::is_valid () const [inline]
```

##### Returns

true if the stored pointer is valid (not NULL).

Definition at line 65 of file [virtqueue](#).

The documentation for this class was generated from the following file:


- l4/l4virtio/virtqueue

## 15.394 L4virtio::Svr::Bad\_descriptor Struct Reference

Exception used by Queue to indicate descriptor errors.

```
#include <virtio>
```

Collaboration diagram for L4virtio::Svr::Bad\_descriptor:



### Public Types

- enum [Error](#) {  
[Bad\\_address](#) , [Bad\\_rights](#) , [Bad\\_flags](#) , [Bad\\_next](#) ,  
[Bad\\_size](#) }

*The error code.*

### Public Member Functions

- [Bad\\_descriptor](#) ([Request\\_processor](#) const \*[proc](#), [Error](#) e)  
*Make a bad descriptor exception.*
- char const \* [message](#) () const  
*Get a human readable description of the error code.*



## Data Fields

- [Request\\_processor](#) const \* **proc**  
*The processor that triggered the exception.*

## 15.394.1 Detailed Description

Exception used by Queue to indicate descriptor errors.

Definition at line [397](#) of file [virtio](#).

## 15.394.2 Member Enumeration Documentation

### 15.394.2.1 Error

```
enum L4virtio::Svr::Bad_descriptor::Error
```

The error code.

#### Enumerator

Bad_address	Address cannot be translated.
Bad_rights	Missing access rights on memory.
Bad_flags	Invalid combination of descriptor flags.
Bad_next	Invalid next index.
Bad_size	Invalid size of memory block.

Definition at line [400](#) of file [virtio](#).

## 15.394.3 Constructor & Destructor Documentation

### 15.394.3.1 Bad\_descriptor()

```
L4virtio::Svr::Bad_descriptor::Bad_descriptor (  
    Request\_processor const * proc,  
    Error e) [inline]
```

Make a bad descriptor exception.

#### Parameters

<i>proc</i>	The request processor causing the exception
<i>e</i>	The error code.

Definition at line [421](#) of file [virtio](#).

References [proc](#).

## 15.394.4 Member Function Documentation

### 15.394.4.1 message()

```
char const * L4virtio::Svr::Bad_descriptor::message () const [inline]
```

Get a human readable description of the error code.

#### Returns


Message describing the error.

Definition at line 430 of file [virtio](#).

References [Bad\\_address](#), [Bad\\_flags](#), [Bad\\_next](#), [Bad\\_rights](#), and [Bad\\_size](#).

Referenced by [Virtio\\_switch::handle\\_l4virtio\\_port\\_tx\(\)](#).

Here is the caller graph for this function:



The documentation for this struct was generated from the following file:


- `l4/l4virtio/server/virtio`

## 15.395 L4virtio::Svr::Block\_dev\_base< Ds\_data > Class Template Reference


Base class for virtio block devices.

```
#include <virtio-block>
```

Inheritance diagram for L4virtio::Svr::Block\_dev\_base< Ds\_data >:



Collaboration diagram for L4virtio::Svr::Block\_dev\_base< Ds\_data >:



## Public Member Functions

- `Block_dev_base` (`l4_uint32_t` vendor, unsigned queue\_size, `l4_uint64_t` capacity, bool read\_only)  
Create a new virtio block device.
- virtual void **reset\_device** ()=0  
Reset the actual hardware device.
- virtual bool **queue\_stopped** ()=0

- *Return true, if the queues should not be processed further.*
- void **finalize\_request** (cxx::unique\_ptr< Request > req, unsigned sz, l4\_uint8\_t status=L4VIRTIO\_BLOCK\_S\_OK)  
*Releases resources related to a request and notifies the client.*
- int **reconfig\_queue** (unsigned idx) override  
*callback for client queue-config request*
- void **reset** () override  
*reset callback, called for doing a device reset*

## Public Member Functions inherited from L4virtio::Svr::Device\_t< Ds\_data >

- virtual bool **check\_features** ()  
*callback for checking the subset of accepted features*
- virtual void **cfg\_changed** (unsigned)  
*callback for client device configuration changes*
- virtual L4::Cap< L4::Irq > **device\_notify\_irq** () const  
*callback to gather the device notification IRQ (old-style)*
- virtual void **register\_driver\_irq** (unsigned idx)  
*Callback for registering an notification IRQ (multi IRQ).*
- virtual unsigned **num\_events\_supported** () const  
*Return the highest notification index supported.*
- **Device\_t** (Dev\_config \*dev\_config)  
*Make a device for the given config.*
- Mem\_list const \* **mem\_info** () const  
*Get the memory region list used for this device.*
- void **reset\_queue\_config** (unsigned idx, unsigned num\_max, bool inc\_generation=false, unsigned device\_notify\_index=0)  
*Trigger reset for the configuration space for queue idx.*
- void **init\_mem\_info** (unsigned num)  
*Initialize the memory region list to the given maximum.*
- void **device\_error** ()  
*Transition device into DEVICE\_NEEDS\_RESET state.*
- bool **setup\_queue** (Virtqueue \*q, unsigned qn, unsigned num\_max)  
*Enable/disable the specified queue.*
- bool **handle\_mem\_cmd\_write** ()  
*Check for a value in the cmd register and handle a write.*
- void **enable\_trusted\_ds\_validation** ()  
*Enable trusted dataspace validation.*
- void **add\_trusted\_dataspaces** (std::shared\_ptr< Ds\_vector const > ds)  
*Provide a list of trusted dataspace that can be used for validation.*

## Protected Member Functions

- void **set\_size\_max** (l4\_uint32\_t sz)  
*Sets the maximum size of any single segment reported to client.*
- void **set\_seg\_max** (l4\_uint32\_t sz)  
*Sets the maximum number of segments in a request that is reported to client.*
- void **set\_geometry** (l4\_uint16\_t cylinders, l4\_uint8\_t heads, l4\_uint8\_t sectors)  
*Set disk geometry that is reported to the client.*
- void **set\_blk\_size** (l4\_uint32\_t sz)

*Sets block disk size to be reported to the client.*

- void `set_topology` (`l4_uint8_t` physical\_block\_exp, `l4_uint8_t` alignment\_offset, `l4_uint32_t` min\_io\_size, `l4_uint32_t` opt\_io\_size)

*Sets the I/O alignment information reported back to the client.*

- void `set_flush` ()

*Enables the flush command.*

- void `set_config_wce` (`l4_uint8_t` writeback)

*Sets cache mode and enables the writeback toggle.*

- `l4_uint8_t` `get_writeback` ()

*Get the writeback field from the configuration space.*

- void `set_discard` (`l4_uint32_t` max\_discard\_sectors, `l4_uint32_t` max\_discard\_seg, `l4_uint32_t` discard\_↵ sector\_alignment)

*Sets constraints for and enables the discard command.*

- void `set_write_zeroes` (`l4_uint32_t` max\_write\_zeroes\_sectors, `l4_uint32_t` max\_write\_zeroes\_seg, `l4_uint8_t` write\_zeroes\_may\_unmap)

*Sets constraints for and enables the write zeroes command.*

- `cxx::unique_ptr< Request >` `get_request` ()

*Return one request if available.*

## Additional Inherited Members

## Protected Attributes inherited from `L4virtio::Svr::Device_t< Ds_data >`

- `Mem_list` `_mem_info`

*Memory region list.*

## 15.395.1 Detailed Description

```
template<typename Ds_data>
class L4virtio::Svr::Block_dev_base< Ds_data >
```

Base class for virtio block devices.

Use this class as a base to implement your own specific block device.

Definition at line 259 of file `virtio-block`.

## 15.395.2 Constructor & Destructor Documentation

### 15.395.2.1 `Block_dev_base()`

```
template<typename Ds_data>
L4virtio::Svr::Block_dev_base< Ds_data >::Block_dev_base (
    l4_uint32_t vendor,
    unsigned queue_size,
    l4_uint64_t capacity,
    bool read_only) [inline]
```

Create a new virtio block device.


**Parameters**

<i>vendor</i>	Vendor ID
<i>queue_size</i>	Number of entries to provide in avail and used queue.
<i>capacity</i>	Size of the device in 512-byte sectors.
<i>read_only</i>	True, if the device should not be writable.

Definition at line 444 of file [virtio-block](#).

References [L4virtio::Svr::Device\\_t< Ds\\_data >::Device\\_t\(\)](#), [L4VIRTIO\\_FEATURE\\_VERSION\\_1](#), [L4VIRTIO\\_ID\\_BLOCK](#), and [L4virtio::Svr::Device\\_t< Ds\\_data >::reset\\_queue\\_config\(\)](#).

Here is the call graph for this function:

**15.395.3 Member Function Documentation****15.395.3.1 finalize\_request()**

```

template<typename Ds_data>
void L4virtio::Svr::Block_dev_base< Ds_data >::finalize_request (
    cxx::unique_ptr< Request > req,
    unsigned sz,
    l4_uint8_t status = L4VIRTIO_BLOCK_S_OK) [inline]
  
```

Releases resources related to a request and notifies the client.

**Parameters**


<i>req</i>	Pointer to request that has finished.
<i>sz</i>	Number of bytes consumed.
<i>status</i>	Status of request (see <a href="#">L4virtio_block_status</a> ).

This function must be called when an asynchronous request finishes, either successfully or with an error. The status byte in the request must have been set prior to calling it.

Definition at line 483 of file [virtio-block](#).

References [L4virtio::Svr::Device\\_t<Ds\\_data>::device\\_error\(\)](#), [L4VIRTIO\\_BLOCK\\_S\\_OK](#), [L4VIRTIO\\_IRQ\\_STATUS\\_VRING](#), and [L4virtio::Virtqueue::no\\_notify\\_guest\(\)](#).

Here is the call graph for this function:



### 15.395.3.2 `get_writeback()`

```
template<typename Ds_data>
l4_uint8_t L4virtio::Svr::Block_dev_base<Ds_data>::get_writeback () [inline], [protected]
```

Get the writeback field from the configuration space.

#### Returns

Value of the writeback field.

Definition at line 388 of file [virtio-block](#).

### 15.395.3.3 `set_blk_size()`

```
template<typename Ds_data>
void L4virtio::Svr::Block_dev_base<Ds_data>::set_blk_size (
    l4_uint32_t sz) [inline], [protected]
```

Sets block disk size to be reported to the client.

Setting this does not change the logical sector size used for addressing the device.

Definition at line 332 of file [virtio-block](#).



#### 15.395.3.4 set\_config\_wce()

```
template<typename Ds_data>
void L4virtio::Svr::Block_dev_base< Ds_data >::set_config_wce (
    14_uint8_t writeback) [inline], [protected]
```

Sets cache mode and enables the writeback toggle.

##### Parameters

<i>writeback</i>	Mode of the cache (0 for writethrough, 1 for writeback).
------------------	--

Definition at line 375 of file [virtio-block](#).

#### 15.395.3.5 set\_discard()

```
template<typename Ds_data>
void L4virtio::Svr::Block_dev_base< Ds_data >::set_discard (
    14_uint32_t max_discard_sectors,
    14_uint32_t max_discard_seg,
    14_uint32_t discard_sector_alignment) [inline], [protected]
```

Sets constraints for and enables the discard command.

##### Parameters

<i>max_discard_sectors</i>	Maximum discard sectors size.
<i>max_discard_seg</i>	Maximum discard segment number.
<i>discard_sector_alignment</i>	Can be used by the driver when splitting a request based on alignment.

Definition at line 402 of file [virtio-block](#).

#### 15.395.3.6 set\_size\_max()

```
template<typename Ds_data>
void L4virtio::Svr::Block_dev_base< Ds_data >::set_size_max (
    14_uint32_t sz) [inline], [protected]
```

Sets the maximum size of any single segment reported to client.

The limit is also applied to any incoming requests. Requests with larger segments result in an IO error being reported to the client. That means that `process_request()` can safely make the assumption that all segments in the received request are smaller.

Definition at line 290 of file [virtio-block](#).

### 15.395.3.7 set\_topology()

```
template<typename Ds_data>
void L4virtio::Svr::Block_dev_base< Ds_data >::set_topology (
    l4_uint8_t physical_block_exp,
    l4_uint8_t alignment_offset,
    l4_uint32_t min_io_size,
    l4_uint32_t opt_io_size) [inline], [protected]
```

Sets the I/O alignment information reported back to the client.

#### Parameters

<i>physical_block_exp</i>	Number of logical blocks per physical block(log2)
<i>alignment_offset</i>	Offset of the first aligned logical block
<i>min_io_size</i>	Suggested minimum I/O size in blocks
<i>opt_io_size</i>	Optimal I/O size in blocks

Definition at line 348 of file [virtio-block](#).

### 15.395.3.8 set\_write\_zeroes()

```
template<typename Ds_data>
void L4virtio::Svr::Block_dev_base< Ds_data >::set_write_zeroes (
    l4_uint32_t max_write_zeroes_sectors,
    l4_uint32_t max_write_zeroes_seg,
    l4_uint8_t write_zeroes_may_unmap) [inline], [protected]
```

Sets constraints for and enables the write zeroes command.

#### Parameters

<i>max_write_zeroes_sectors</i>	Maximum write zeroes sectors size.
<i>max_write_zeroes_seg</i>	maximum write zeroes segment number.
<i>write_zeroes_may_unmap</i>	Set if a write zeroes request can result in deallocating one or more sectors.

Definition at line 422 of file [virtio-block](#).

The documentation for this class was generated from the following file:

- I4/I4virtio/server/virtio-block

## 15.396 L4virtio::Svr::Block\_request< Ds\_data > Class Template Reference

A request to read or write data.

```
#include <virtio-block>
```

Collaboration diagram for L4virtio::Svr::Block\_request< Ds\_data >:

L4virtio::Svr::Block_request< Ds_data >
<ul style="list-style-type: none"> <li>+ data_size()</li> <li>+ has_more()</li> <li>+ next_block()</li> <li>+ header()</li> </ul>

### Public Member Functions

- unsigned [data\\_size](#) () const  
*Compute the total size of the data in the request.*
- bool **has\_more** ()  
*Check if the request contains more data blocks.*
- Data\_block [next\\_block](#) ()  
*Return next block in scatter-gather list.*
- [l4virtio\\_block\\_header\\_t](#) const & **header** () const  
*Return the block request header.*

### 15.396.1 Detailed Description

```
template<typename Ds_data>
class L4virtio::Svr::Block_request< Ds_data >
```

A request to read or write data.

Definition at line 28 of file [virtio-block](#).

## 15.396.2 Member Function Documentation

### 15.396.2.1 data\_size()

```
template<typename Ds_data>
unsigned L4virtio::Svr::Block_request< Ds_data >::data_size () const [inline]
```

Compute the total size of the data in the request.

#### Return values

Size	in bytes or 0 if there was an error.
------	--------------------------------------

#### Exceptions


<a href="#">L4::Runtime_error(-L4_EIO)</a>	Request has a bad format.
--	---------------------------

Note that this operation is relatively expensive as it has to iterate over the complete list of blocks.

Definition at line 63 of file [virtio-block](#).

References [L4virtio::Svr::Request\\_processor::has\\_more\(\)](#), [L4\\_EIO](#), [L4virtio::Svr::Request\\_processor::next\(\)](#), and [L4virtio::Svr::Request\\_processor::start\(\)](#).

Here is the call graph for this function:



### 15.396.2.2 next\_block()

```
template<typename Ds_data>
Data_block L4virtio::Svr::Block_request< Ds_data >::next_block () [inline]
```

Return next block in scatter-gather list.

### Returns

Information about the next data block.

### Exceptions

<a href="#">L4::Runtime_error</a>	No more data block is available.
<a href="#">Bad_descriptor</a>	Virtio request is corrupted.

Definition at line 113 of file [virtio-block](#).

References [L4virtio::Svr::Bad\\_descriptor::Bad\\_size](#), and [L4\\_EEXIST](#).

The documentation for this class was generated from the following file:


- I4/I4virtio/server/virtio-block

## 15.397 L4virtio::Svr::Console::Control\_message Struct Reference

Virtio console control message.

```
#include <virtio-console>
```

Collaboration diagram for L4virtio::Svr::Console::Control\_message:



### Public Types

- enum [Events](#) {  
    [Device\\_ready](#) = 0 , [Device\\_add](#) = 1 , [Device\\_remove](#) = 2 , [Port\\_ready](#) = 3 ,  
    [Console\\_port](#) = 4 , [Resize](#) = 5 , [Port\\_open](#) = 6 , [Port\\_name](#) = 7 }

*Possible control events.*

## Data Fields

- [l4\\_uint32\\_t id](#)  
*Port number.*
- [l4\\_uint16\\_t event](#)  
*Control event, see [Events](#).*
- [l4\\_uint16\\_t value](#)  
*Extra information.*

### 15.397.1 Detailed Description

Virtio console control message.

Definition at line 31 of file [virtio-console](#).

### 15.397.2 Member Enumeration Documentation

#### 15.397.2.1 Events

```
enum L4virtio::Svr::Console::Control_message::Events
```

Possible control events.

#### Enumerator

Device_ready	Sent by driver at initialization.
Device_add	Sent by device to create new ports.
Device_remove	Sent by device to remove added ports.
Port_ready	Sent by driver as response to <a href="#">Device_add</a> .
Console_port	Sent by device to nominate port as console port.
Resize	Sent by device to indicate a console size change.
Port_open	Sent by device and driver to indicate whether a port is open.
Port_name	Sent by device to tag a port.

Definition at line 34 of file [virtio-console](#).

The documentation for this struct was generated from the following file:


- [l4/l4virtio/server/virtio-console](#)

## 15.398 L4virtio::Svr::Console::Control\_request Struct Reference

Specialised `Virtqueue::Request` providing access to control message payload.

```
#include <virtio-console>
```

Collaboration diagram for L4virtio::Svr::Console::Control\_request:



## Data Fields

- [Control\\_message](#) \* **msg**  
*Virtual address of the data block (in device space).*
- [l4\\_uint32\\_t](#) **len**  
*Length of datablock in bytes.*
- [Driver\\_mem\\_region](#) \* **mem**  
*Pointer to driver memory region.*

### 15.398.1 Detailed Description

Specialised `Virtqueue::Request` providing access to control message payload.

Definition at line 65 of file [virtio-console](#).

The documentation for this struct was generated from the following file:

- `l4/l4virtio/server/virtio-console`


## 15.399 L4virtio::Svr::Console::Device Class Reference

Base class implementing a virtio console device with L4Re-based notification handling.


```
#include <virtio-console-device>
```



Inheritance diagram for L4virtio::Svr::Console::Device:



Collaboration diagram for L4virtio::Svr::Console::Device:



## Public Member Functions

- [Device](#) (unsigned vq\_max)  
Create a new console device.
- [Device](#) (unsigned vq\_max, unsigned ports)  
Create a new console device.
- [Device](#) (cx::static\_vector< unsigned > const &vq\_max\_nums)

- Create a new console [Device](#).
- void **register\_single\_driver\_irq** () override  
callback for registering a single guest IRQ for all queues (old-style)
- [L4::Cap](#)< [L4::Irq](#) > **device\_notify\_irq** () const override  
callback to gather the device notification IRQ (old-style)
- void **notify\_queue** (Virtqueue \*queue) override  
Notify queue of available data.
- virtual void **rx\_data\_available** (unsigned [port](#))=0  
Callback to notify that new data is available to be read from port.
- virtual void **tx\_space\_available** (unsigned [port](#))=0  
Callback to notify that data can be written to port.
- virtual bool **queues\_stopped** ()  
Return true, if the queues should not be processed further.
- void **trigger\_driver\_config\_irq** () override  
callback for triggering configuration change notification IRQ
- unsigned [port\\_read](#) (char \*buf, unsigned len, unsigned [port](#)=0)  
Read data from port.
- unsigned [port\\_write](#) (char const \*buf, unsigned len, unsigned [port](#)=0)  
Write data to port.
- void **process\_device\_ready** ([l4\\_uint16\\_t](#) value) override  
Callback called on `DEVICE_READY` event.
- void **process\_port\_ready** ([l4\\_uint32\\_t](#) id, [l4\\_uint16\\_t](#) value) override  
Callback called on `PORT_READY` event.
- void **process\_port\_open** ([l4\\_uint32\\_t](#) id, [l4\\_uint16\\_t](#) value) override  
Callback called on `PORT_OPEN` event.

## Public Member Functions inherited from [L4virtio::Svr::Console::Virtio\\_con](#)

- [Virtio\\_con](#) (unsigned max\_ports, bool enable\_multiport)  
Create a new multiport console device.
- int **reconfig\_queue** (unsigned index) override  
callback for client queue-config request
- bool **multiport\_enabled** () const  
Return true if the multiport feature is enabled and control queues are available.
- bool **check\_features** (void) override  
callback for checking the subset of accepted features
- bool **check\_queues** () override  
callback for checking if the queues at `DRIVER_OK` transition
- int [port\\_add](#) (unsigned idx)  
Send a `DEVICE_ADD` message and update the internal state.
- int [port\\_remove](#) (unsigned idx)  
Send a `DEVICE_REMOVE` message and update the internal state.
- int [port\\_open](#) (unsigned idx, bool open)  
Send a `PORT_OPEN` message and update the internal state.
- int [port\\_name](#) (unsigned idx, char const \*name)  
Send a `PORT_NAME` message to announce the port name.
- int [send\\_control\\_message](#) ([l4\\_uint32\\_t](#) idx, [l4\\_uint16\\_t](#) event, [l4\\_uint16\\_t](#) value=0, const char \*name=0)  
Send control message to driver.
- int [handle\\_control\\_message](#) ()  
Handle control message received from the driver.
- void **reset** () override  
reset callback, called for doing a device reset
- virtual void [reset\\_device](#) ()  
Reset the state of the actual console device.

## Public Member Functions inherited from [L4virtio::Svr::Device\\_t< No\\_custom\\_data >](#)

- virtual void **cfg\_changed** (unsigned)  
*callback for client device configuration changes*
- virtual void **register\_driver\_irq** (unsigned idx)  
*Callback for registering an notification IRQ (multi IRQ).*
- virtual [L4::Cap< L4::Irq >](#) **device\_notify\_irq** (unsigned idx)  
*Callback to gather the device notification IRQ (multi IRQ).*
- virtual unsigned **num\_events\_supported** () const  
*Return the highest notification index supported.*
- **Device\_t** ([Dev\\_config](#) \*dev\_config)  
*Make a device for the given config.*
- [Mem\\_list](#) const \* **mem\_info** () const  
*Get the memory region list used for this device.*
- void **reset\_queue\_config** (unsigned idx, unsigned num\_max, bool inc\_generation=false, unsigned device\_notify\_index=0)  
*Trigger reset for the configuration space for queue idx.*
- void **init\_mem\_info** (unsigned num)  
*Initialize the memory region list to the given maximum.*
- void **device\_error** ()  
*Transition device into DEVICE\_NEEDS\_RESET state.*
- bool **setup\_queue** ([Virtqueue](#) \*q, unsigned qn, unsigned num\_max)  
*Enable/disable the specified queue.*
- bool **handle\_mem\_cmd\_write** ()  
*Check for a value in the cmd register and handle a write.*
- void **enable\_trusted\_ds\_validation** ()  
*Enable trusted dataspace validation.*
- void **add\_trusted\_dataspaces** ([std::shared\\_ptr< Ds\\_vector const >](#) ds)  
*Provide a list of trusted dataspaces that can be used for validation.*

## Protected Member Functions

- [Port](#) \* **port** (unsigned idx) override  
*Return the specified port.*

## Additional Inherited Members

## Protected Attributes inherited from [L4virtio::Svr::Device\\_t< No\\_custom\\_data >](#)

- [Mem\\_list](#) **\_mem\_info**  
*Memory region list.*

## 15.399.1 Detailed Description

Base class implementing a virtio console device with L4Re-based notification handling.

This console device is derived from [Virtio\\_con](#) and already includes functionality to handle interrupts and notify drivers. If an interrupt is received, all the necessary interaction with the virtqueues is performed and only the actual data processing has to be done by the derived class. By default all available ports are added and an "open"-request of a port by the driver is automatically acknowledged. The derived class can optionally change this behaviour by overriding [process\\_device\\_ready\(\)](#), [process\\_port\\_ready\(\)](#) and [process\\_port\\_open\(\)](#).

This class provides a stream-based interface to access the port data with edge-triggered notification callbacks. If a port receives data from the driver the derived class is notified with the [rx\\_data\\_available\(\)](#) callback. The actual data can be retrieved by [port\\_read\(\)](#). If there was not enough data to be read, the call will return the available partial data. Only then will the [rx\\_data\\_available\(\)](#) callback be triggered again.

Data on a port may be transmitted by [port\\_write\(\)](#). If there were not enough buffers available, only a part of the data will be transmitted. Once there are new buffers available, the [tx\\_space\\_available\(\)](#) callback will be invoked. This callback will be called again only after a previous [port\\_write\(\)](#) was not able to send all requested data.

Use this class as a base to provide your own high-level console device. You must derive from this class as well as [L4::Epiface\\_t<..., L4virtio::Device>](#). For a working device the [irq\\_iface\(\)](#) must be registered too. A typical implementation might look like the following:

```
class My_console
: public L4virtio::Svr::Console::Device,
  public L4::Epiface_t<My_console, L4virtio::Device>
{
public:
    My_console(L4Re::Util::Object_registry *r)
    : L4virtio::Svr::Console::Device(0x100)
    {
        init_mem_info(4);
        L4Re::chkcap(r->register_irq_obj(irq_iface()), "virtio notification IRQ");
    }

    void rx_data_available(unsigned port) override
    {
        // call port_read() to fetch available data
    }

    void tx_space_available(unsigned port) override
    {
        // can call port_write() to send (pending) data
    }
};

My_console console(registry);
registry->register_obj(&console, ...);
```

The maximum number of memory regions ([init\\_mem\\_info\(\)](#)) should correlate with the number of supported ports.

Definition at line 118 of file [virtio-console-device](#).

## 15.399.2 Constructor & Destructor Documentation

### 15.399.2.1 Device() [1/3]

```
L4virtio::Svr::Console::Device::Device (
    unsigned vq_max) [inline], [explicit]
```

Create a new console device.

**Parameters**


<i>vq_max</i>	Maximum number of buffers in data queues.
---------------	---

Create a console device with no multiport support, i.e. control queues are disabled.

Definition at line 145 of file [virtio-console-device](#).

References [L4virtio::Svr::Console::Virtio\\_con::Virtio\\_con\(\)](#).

Here is the call graph for this function:

**15.399.2.2 Device() [2/3]**

```
L4virtio::Svr::Console::Device::Device (
    unsigned vq_max,
    unsigned ports) [inline], [explicit]
```

Create a new console device.

**Parameters**


<i>vq_max</i>	Maximum number of buffers in data queues.
<i>ports</i>	Number of ports (maximum 32).

Create a console device with multiport support, i.e. control queues are enabled.

Definition at line 163 of file [virtio-console-device](#).

References [L4virtio::Svr::Console::Virtio\\_con::Virtio\\_con\(\)](#).

Here is the call graph for this function:



### 15.399.2.3 Device() [3/3]

```
L4virtio::Svr::Console::Device::Device (
    cxx::static_vector< unsigned > const & vq_max_nums) [inline], [explicit]
```

Create a new console [Device](#).

#### Parameters


<i>vq_max_nums</i>	Maximum number of buffers in data queues, given as a <a href="#">cxx::static_vector</a> with one entry per port.
--------------------	--

Create a console device with multiport support, i.e. control queues are enabled.

Definition at line 182 of file [virtio-console-device](#).

References [L4virtio::Svr::Console::Virtio\\_con::Virtio\\_con\(\)](#).

Here is the call graph for this function:



## 15.399.3 Member Function Documentation

### 15.399.3.1 notify\_queue()

```
void L4virtio::Svr::Console::Device::notify_queue (
    Virtqueue * queue) [inline], [override], [virtual]
```

Notify queue of available data.

#### Parameters

<i>queue</i>	<a href="#">Virtqueue</a> to notify.
--------------	--------------------------------------


This callback is called whenever data is sent to `queue`. It is the responsibility of the derived class to perform all necessary notification actions, e.g. triggering guest interrupts.

Implements [L4virtio::Svr::Console::Virtio\\_con](#).

Definition at line 202 of file [virtio-console-device](#).

References [L4VIRTIO\\_IRQ\\_STATUS\\_VRING](#), and [L4virtio::Virtqueue::no\\_notify\\_guest\(\)](#).

Here is the call graph for this function:



### 15.399.3.2 `port()`

```
Port * L4virtio::Svr::Console::Device::port (
    unsigned port) [inline], [override], [protected], [virtual]
```

Return the specified port.

#### Parameters

<i>port</i>	Port number.
-------------	--------------

#### Precondition

Port number must be lower than the configured maximum number of ports.


Implements [L4virtio::Svr::Console::Virtio\\_con](#).

Definition at line 450 of file [virtio-console-device](#).

Referenced by [port\\_read\(\)](#), [port\\_write\(\)](#), [process\\_port\\_ready\(\)](#), [rx\\_data\\_available\(\)](#), and [tx\\_space\\_available\(\)](#).



Here is the caller graph for this function:



### 15.399.3.3 port\_read()

```

unsigned L4virtio::Svr::Console::Device::port_read (
    char * buf,
    unsigned len,
    unsigned port = 0) [inline]
  
```

Read data from port.

Will read up to *len* bytes from *port* into *buf*. Returns the number of bytes read, which may be less if not enough data was available. If all data was read, the [rx\\_data\\_available\(\)](#) callback will be invoked the next time the driver queues new data for the port. The callback won't be called again until all data was consumed again.

#### Parameters

<i>buf</i>	The destination buffer
<i>len</i>	Size of the buffer
<i>port</i>	<a href="#">Port</a> index to read data from


## Returns

Number of bytes read

Definition at line 272 of file [virtio-console-device](#).

References [L4virtio::Svr::Data\\_buffer::copy\\_to\(\)](#), [L4virtio::Svr::Device\\_t< No\\_custom\\_data >::device\\_error\(\)](#), [L4virtio::Svr::Virtqueue::finish\(\)](#), [L4virtio::Svr::Data\\_buffer::left](#), [L4virtio::Svr::Device\\_t< No\\_custom\\_data >::mem\\_info\(\)](#), [L4virtio::Svr::Request\\_processor::next\(\)](#), [L4virtio::Svr::Virtqueue::next\\_avail\(\)](#), [port\(\)](#), [L4virtio::Svr::Data\\_buffer::pos](#), [L4virtio::Svr::Console::Device\\_port::request](#), [L4virtio::Svr::Console::Device\\_port::rp](#), [L4virtio::Svr::Console::Device\\_port::src](#), [L4virtio::Svr::Request\\_processor::start\(\)](#), [L4virtio::Svr::Console::Port::tx](#), [L4virtio::Svr::Console::Port::tx\\_ready\(\)](#), and [L4virtio::Svr::Virtqueue::Head\\_desc::valid\(\)](#).

Here is the call graph for this function:



### 15.399.3.4 port\_write()

```

unsigned L4virtio::Svr::Console::Device::port_write (
    char const * buf,
    unsigned len,
    unsigned port = 0) [inline]

```

Write data to port.

Will write up to *len* bytes to *port* from *buf*. Returns the number of bytes written, which may be less if not enough virtio buffers were available. If not all data could be written, the [tx\\_space\\_available\(\)](#) callback will be invoked the next time the driver queues new receive buffers for the port. The callback won't be called again until all receive buffers were filled again.

#### Parameters

<i>buf</i>	The souce buffer
<i>len</i>	Size of the buffer
<i>port</i>	<a href="#">Port</a> index to write data to


#### Returns

Number of bytes written

Definition at line 341 of file [virtio-console-device](#).

References [L4virtio::Svr::Data\\_buffer::copy\\_to\(\)](#), [L4virtio::Svr::Device\\_t< No\\_custom\\_data >::device\\_error\(\)](#), [L4virtio::Svr::Virtqueue::finish\(\)](#), [L4virtio::Svr::Data\\_buffer::left](#), [L4virtio::Svr::Device\\_t< No\\_custom\\_data >::mem\\_info\(\)](#), [L4virtio::Svr::Request\\_processor::next\(\)](#), [L4virtio::Svr::Virtqueue::next\\_avail\(\)](#), [port\(\)](#), [L4virtio::Svr::Data\\_buffer::pos](#), [L4virtio::Svr::Console::Port::rx](#), [L4virtio::Svr::Console::Port::rx\\_ready\(\)](#), and [L4virtio::Svr::Request\\_processor::start\(\)](#).

Here is the call graph for this function:



### 15.399.3.5 process\_device\_ready()

```
void L4virtio::Svr::Console::Device::process_device_ready (
    l4_uint16_t value) [inline], [override], [virtual]
```

Callback called on DEVICE\_READY event.

#### Parameters

<i>value</i>	The value field of the control message, indicating if the initialization was successful.
--------------	--


By default, this function adds all ports if the driver indicates successful initialization. Override this function to perform custom actions for a DEVICE\_READY event. It is then your responsibility to inform the driver about usable ports, see [port\\_add\(\)](#).

Implements [L4virtio::Svr::Console::Virtio\\_con](#).

Definition at line 399 of file [virtio-console-device](#).

References [L4virtio::Svr::Console::Virtio\\_con::port\\_add\(\)](#).

Here is the call graph for this function:



### 15.399.3.6 process\_port\_open()

```
void L4virtio::Svr::Console::Device::process_port_open (
    14_uint32_t id,
    14_uint16_t value) [inline], [override], [virtual]
```

Callback called on PORT\_OPEN event.

#### Parameters

<i>id</i>	The id field of the control message, i.e. the port number.
<i>value</i>	The value field of the control message, indicating if the port was opened or closed.

The default implementation does nothing. Override it to implement some custom logic to respond to open/close events of the driver.

Implements [L4virtio::Svr::Console::Virtio\\_con](#).

Definition at line 443 of file [virtio-console-device](#).

### 15.399.3.7 process\_port\_ready()

```
void L4virtio::Svr::Console::Device::process_port_ready (
    14_uint32_t id,
    14_uint16_t value) [inline], [override], [virtual]
```

Callback called on PORT\_READY event.

#### Parameters

<i>id</i>	The id field of the control message, i.e. the port number.
<i>value</i>	The value field of the control message, indicating if the initialization was successful.

By default, this function opens the port if the driver is ready. Otherwise, the port is removed if the driver failed to set it up correctly. Override this function to perform custom actions for a PORT\_READY event, *after* the generic


management of the base class. It is then your responsibility to inform the driver about connected or unusable ports. See `port_open()` and `port_remove()`.

Reimplemented from `L4virtio::Svr::Console::Virtio_con`.

Definition at line 422 of file `virtio-console-device`.

References `port()`, `L4virtio::Svr::Console::Port::Port_failed`, `L4virtio::Svr::Console::Virtio_con::port_open()`, `L4virtio::Svr::Console::Port::Port_ready`, `L4virtio::Svr::Console::Virtio_con::port_remove()`, `L4virtio::Svr::Console::Virtio_con::process`, and `L4virtio::Svr::Console::Port::status`.

Here is the call graph for this function:



The documentation for this class was generated from the following file:


- `I4/I4virtio/server/virtio-console-device`

## 15.400 L4virtio::Svr::Console::Device\_port Struct Reference


A console port with associated read/write state.

```
#include <virtio-console-device>
```

Inheritance diagram for L4virtio::Svr::Console::Device\_port:



Collaboration diagram for L4virtio::Svr::Console::Device\_port:



## Public Member Functions

- void **reset** () override  
*Reset the port to the initial state and disable its virtqueues.*

## Public Member Functions inherited from L4virtio::Svr::Console::Port

- bool **is\_open** () const



*Check that the port is open.*

- bool **queues\_ready** () const

*Check that both virtqueues are set up correctly.*

- bool **rx\_ready** () const

*Check that device implementation may write to receive queues.*

- bool **tx\_ready** () const

*Check that device implementation may read from transmit queues.*

## Data Fields

- [Request\\_processor](#) **rp**

*Request processor associated with current request.*

- Virtqueue::Request **request**

*Current virtio tx queue request.*

- [Buffer](#) **src**

*Source data block to process.*

## Data Fields inherited from [L4virtio::Svr::Console::Port](#)

- Virtqueue **tx**

*Receiveq of the port.*

- Virtqueue **rx**

*Transmitq of the port.*

- [Port\\_status](#) **status**

*State the port is in.*

- [Port\\_status](#) **reported\_status**

*State the port was last reported.*

- unsigned **vq\_max**

*Maximum queue sizes for this port.*

## Additional Inherited Members

## Public Types inherited from [L4virtio::Svr::Console::Port](#)

- enum [Port\\_status](#) {  
[Port\\_disabled](#) = 0 , [Port\\_added](#) , [Port\\_ready](#) , [Port\\_open](#) ,  
[Port\\_failed](#) , [Port\\_num\\_states](#) }

*Possible states of a virtio console port.*

- enum

*Size of control queues, also used as default size.*

## Static Public Attributes inherited from [L4virtio::Svr::Console::Port](#)

- static constexpr [Transition state\\_transitions](#) [[Port\\_num\\_states](#)][[Port\\_num\\_states](#)]

*State transition table from last report state to current state.*

### 15.400.1 Detailed Description

A console port with associated read/write state.

Tracks the notification of the device implementation and holds the state when receiving data from the driver.

Definition at line 26 of file [virtio-console-device](#).

The documentation for this struct was generated from the following file:


- `l4/l4virtio/server/virtio-console-device`

## 15.401 L4virtio::Svr::Console::Features Struct Reference


Virtio console specific feature bits.

```
#include <virtio-console>
```

Inheritance diagram for L4virtio::Svr::Console::Features:



Collaboration diagram for L4virtio::Svr::Console::Features:



- typedef `cxx::Bitfield< decltype(raw), 0, 0 >` `console_size_bfm_t`  
Configuration `cols` and `rows` are valid.
- constexpr `console_size_bfm_t::Val console_size ()` const  
Get the `console_size` bits (0 to 0) of `raw`.
- constexpr `console_size_bfm_t::Ref console_size ()`  
Get a reference to the `console_size` bits (0 to 0) of `raw`.
- typedef `cxx::Bitfield< decltype(raw), 1, 1 >` `console_multiport_bfm_t`  
`Device` has support for multiple ports.
- constexpr `console_multiport_bfm_t::Val console_multiport ()` const  
Get the `console_multiport` bits (1 to 1) of `raw`.

- constexpr [console\\_multiport\\_bfm\\_t::Ref](#) **console\_multiport** ()  
*Get a reference to the [console\\_multiport](#) bits (1 to 1) of [raw](#).*
- typedef [cxx::Bitfield](#)< decltype([raw](#)), 2, 2 > **emerg\_write\_bfm\_t**  
*[Device](#) has support for emergency write.*
- constexpr [emerg\\_write\\_bfm\\_t::Val](#) **emerg\_write** () const  
*Get the [emerg\\_write](#) bits (2 to 2) of [raw](#).*
- constexpr [emerg\\_write\\_bfm\\_t::Ref](#) **emerg\_write** ()  
*Get a reference to the [emerg\\_write](#) bits (2 to 2) of [raw](#).*

### Additional Inherited Members

- typedef [cxx::Bitfield](#)< decltype([raw](#)), 28, 28 > **ring\_indirect\_desc\_bfm\_t**  
*Type to access the [ring\\_indirect\\_desc](#) bits (28 to 28) of [raw](#).*
- typedef [cxx::Bitfield](#)< decltype([raw](#)), 29, 29 > **ring\_event\_idx\_bfm\_t**  
*Type to access the [ring\\_event\\_idx](#) bits (29 to 29) of [raw](#).*

### Public Member Functions inherited from [L4virtio::Svr::Dev\\_features](#)

- **Dev\_features** ([l4\\_uint32\\_t](#) v)  
*Make Features from a raw bitmap.*
- constexpr [ring\\_indirect\\_desc\\_bfm\\_t::Val](#) **ring\_indirect\_desc** () const  
*Get the [ring\\_indirect\\_desc](#) bits (28 to 28) of [raw](#).*
- constexpr [ring\\_indirect\\_desc\\_bfm\\_t::Ref](#) **ring\_indirect\_desc** ()  
*Get a reference to the [ring\\_indirect\\_desc](#) bits (28 to 28) of [raw](#).*
- constexpr [ring\\_event\\_idx\\_bfm\\_t::Val](#) **ring\_event\_idx** () const  
*Get the [ring\\_event\\_idx](#) bits (29 to 29) of [raw](#).*
- constexpr [ring\\_event\\_idx\\_bfm\\_t::Ref](#) **ring\_event\_idx** ()  
*Get a reference to the [ring\\_event\\_idx](#) bits (29 to 29) of [raw](#).*

### Data Fields inherited from [L4virtio::Svr::Dev\\_features](#)

- [l4\\_uint32\\_t](#) **raw**  
*The raw value of the features bitmap.*

## 15.401.1 Detailed Description

Virtio console specific feature bits.

Definition at line 18 of file [virtio-console](#).

## 15.401.2 Member Typedef Documentation

### 15.401.2.1 console\_multiport\_bfm\_t

```
typedef cxx::Bitfield<decltype(raw), 1, 1> L4virtio::Svr::Console::Features::console_multiport_bfm_t
```

Device has support for multiple ports.

Type to access the `console_multiport` bits (1 to 1) of `raw`.

Definition at line 25 of file `virtio-console`.

### 15.401.2.2 console\_size\_bfm\_t

```
typedef cxx::Bitfield<decltype(raw), 0, 0> L4virtio::Svr::Console::Features::console_size_bfm_t
```

Configuration `cols` and `rows` are valid.

Type to access the `console_size` bits (0 to 0) of `raw`.

Definition at line 23 of file `virtio-console`.

### 15.401.2.3 emerg\_write\_bfm\_t

```
typedef cxx::Bitfield<decltype(raw), 2, 2> L4virtio::Svr::Console::Features::emerg_write_bfm_t
```

Device has support for emergency write.

Type to access the `emerg_write` bits (2 to 2) of `raw`.

Definition at line 27 of file `virtio-console`.

The documentation for this struct was generated from the following file:


- `I4/I4virtio/server/virtio-console`

## 15.402 L4virtio::Svr::Console::Port Struct Reference


Representation of a Virtio console port.

```
#include <virtio-console>
```

Inheritance diagram for L4virtio::Svr::Console::Port:



Collaboration diagram for L4virtio::Svr::Console::Port:



## Data Structures

- struct [Transition](#)

State transition from last report state to current state.



## Public Types

- enum [Port\\_status](#) {  
    [Port\\_disabled](#) = 0 , [Port\\_added](#) , [Port\\_ready](#) , [Port\\_open](#) ,  
    [Port\\_failed](#) , [Port\\_num\\_states](#) }

*Possible states of a virtio console port.*

- enum  
*Size of control queues, also used as default size.*

## Public Member Functions

- bool **is\_open** () const  
*Check that the port is open.*
- virtual void **reset** ()  
*Reset the port to the initial state and disable its virtqueues.*
- bool **queues\_ready** () const  
*Check that both virtqueues are set up correctly.*
- bool **rx\_ready** () const  
*Check that device implementation may write to receive queues.*
- bool **tx\_ready** () const  
*Check that device implementation may read from transmit queues.*

## Data Fields

- Virtqueue **tx**  
*Receiveq of the port.*
- Virtqueue **rx**  
*Transmitq of the port.*
- [Port\\_status](#) **status**  
*State the port is in.*
- [Port\\_status](#) **reported\_status**  
*State the port was last reported.*
- unsigned **vq\_max**  
*Maximum queue sizes for this port.*

## Static Public Attributes


- static constexpr [Transition](#) **state\_transitions** [[Port\\_num\\_states](#)][[Port\\_num\\_states](#)]  
*State transition table from last report state to current state.*

### 15.402.1 Detailed Description

Representation of a Virtio console port.

Each port consists of a pair of queues for sending and receiving.

A port may be added and removed at runtime when the multi-port feature is enabled. The states are as follows:



Definition at line 109 of file [virtio-console](#).

### 15.402.2 Member Enumeration Documentation

#### 15.402.2.1 Port\_status

```
enum L4virtio::Svr::Console::Port::Port_status
```

Possible states of a virtio console port.

#### Enumerator

Port_disabled	Reset state, waiting for port to be added.
Port_added	<a href="#">Port</a> has been added by device, waiting for ready message.
Port_ready	<a href="#">Port</a> is ready but still closed.
Port_open	<a href="#">Port</a> is in a working state.
Port_failed	<a href="#">Device</a> failure, port unusable.
Port_num_states	Number of port states. Must be last.

Definition at line 114 of file [virtio-console](#).

### 15.402.3 Field Documentation

#### 15.402.3.1 state\_transitions

`Transition` L4virtio::Svr::Console::Port::state\_transitions[Port\_num\_states][Port\_num\_states]  
[static], [constexpr]

State transition table from last report state to current state.

Not all transitions can be made directly. For example, if the last reported state was `Port_disabled` and the current state is `Port_open`, the device has to send two messages: `Control_message::Device_add` and `Control_message::Port_open`. This is expressed by going through an intermediate state (`Port_ready`) on the reporting side.

For the purpose of the driver there are only three coarse states:

1. The port does not exist (`Port_disabled`).
2. The port exists but is closed on the device side (`Port_added`, `Port_ready`, `Port_failed`).
3. The port exists and is open on the device side (`Port_open`).

The state transition table with `Port_added`, `Port_ready` and `Port_failed` as current state are thus identical.

Definition at line 195 of file [virtio-console](#).

The documentation for this struct was generated from the following file:

- `l4/l4virtio/server/virtio-console`

## 15.403 L4virtio::Svr::Console::Port::Transition Struct Reference

State transition from last report state to current state.

```
#include <virtio-console>
```

Collaboration diagram for L4virtio::Svr::Console::Port::Transition:

L4virtio::Svr::Console ::Port::Transition	
+	event
+	value
+	next

### Data Fields

- [l4\\_int16\\_t](#) **event**  
*[Control\\_message::Events](#) or  $< 0$  if no event is sent.*
- [l4\\_uint16\\_t](#) **value**  
*Extra information.*
- [Port\\_status](#) **next**  
*Next [Port\\_status](#) state.*

## 15.403.1 Detailed Description

State transition from last report state to current state.

Definition at line [169](#) of file [virtio-console](#).

The documentation for this struct was generated from the following file:


- [l4/l4virtio/server/virtio-console](#)

## 15.404 L4virtio::Svr::Console::Virtio\_con Class Reference

Base class implementing a virtio console functionality.

```
#include <virtio-console>
```

Inheritance diagram for L4virtio::Svr::Console::Virtio\_con:





- Return true if the multiport feature is enabled and control queues are available.*

  - bool **check\_features** (void) override  
*callback for checking the subset of accepted features*
  - bool **check\_queues** () override  
*callback for checking if the queues at DRIVER\_OK transition*
  - int **port\_add** (unsigned idx)  
*Send a DEVICE\_ADD message and update the internal state.*
  - int **port\_remove** (unsigned idx)  
*Send a DEVICE\_REMOVE message and update the internal state.*
  - int **port\_open** (unsigned idx, bool open)  
*Send a PORT\_OPEN message and update the internal state.*
  - int **port\_name** (unsigned idx, char const \*name)  
*Send a PORT\_NAME message to announce the port name.*
  - int **send\_control\_message** (l4\_uint32\_t idx, l4\_uint16\_t event, l4\_uint16\_t value=0, const char \*name=0)  
*Send control message to driver.*
  - int **handle\_control\_message** ()  
*Handle control message received from the driver.*
  - void **reset** () override  
*reset callback, called for doing a device reset*
  - virtual void **reset\_device** ()  
*Reset the state of the actual console device.*
  - virtual void **notify\_queue** (Virtqueue \*queue)=0  
*Notify queue of available data.*
  - virtual Port \* **port** (unsigned port)=0  
*Return the specified port.*
  - virtual void **process\_device\_ready** (l4\_uint16\_t value)=0  
*Callback called on DEVICE\_READY event.*
  - virtual void **process\_port\_ready** (l4\_uint32\_t id, l4\_uint16\_t value)  
*Callback called on PORT\_READY event.*
  - virtual void **process\_port\_open** (l4\_uint32\_t id, l4\_uint16\_t value)=0  
*Callback called on PORT\_OPEN event.*

## Public Member Functions inherited from L4virtio::Svr::Device\_t< No\_custom\_data >

- virtual void **cfg\_changed** (unsigned)  
*callback for client device configuration changes*
- virtual void **register\_single\_driver\_irq** ()  
*callback for registering a single guest IRQ for all queues (old-style)*
- virtual void **trigger\_driver\_config\_irq** ()=0  
*callback for triggering configuration change notification IRQ*
- virtual L4::Cap< L4::Irq > **device\_notify\_irq** () const  
*callback to gather the device notification IRQ (old-style)*
- virtual void **register\_driver\_irq** (unsigned idx)  
*Callback for registering an notification IRQ (multi IRQ).*
- virtual L4::Cap< L4::Irq > **device\_notify\_irq** (unsigned idx)  
*Callback to gather the device notification IRQ (multi IRQ).*
- virtual unsigned **num\_events\_supported** () const  
*Return the highest notification index supported.*
- **Device\_t** (Dev\_config \*dev\_config)  
*Make a device for the given config.*

- `Mem_list const * mem_info () const`  
*Get the memory region list used for this device.*
- `void reset_queue_config (unsigned idx, unsigned num_max, bool inc_generation=false, unsigned device_↵ notify_index=0)`  
*Trigger reset for the configuration space for queue idx.*
- `void init_mem_info (unsigned num)`  
*Initialize the memory region list to the given maximum.*
- `void device_error ()`  
*Transition device into DEVICE\_NEEDS\_RESET state.*
- `bool setup_queue (Virtqueue *q, unsigned qn, unsigned num_max)`  
*Enable/disable the specified queue.*
- `bool handle_mem_cmd_write ()`  
*Check for a value in the cmd register and handle a write.*
- `void enable_trusted_ds_validation ()`  
*Enable trusted dataspace validation.*
- `void add_trusted_dataspaces (std::shared_ptr< Ds_vector const > ds)`  
*Provide a list of trusted dataspaces that can be used for validation.*

## Additional Inherited Members

## Protected Attributes inherited from `L4virtio::Svr::Device_t< No_custom_data >`

- `Mem_list _mem_info`  
*Memory region list.*

### 15.404.1 Detailed Description

Base class implementing a virtio console functionality.

It is possible to activate the MULTIPORT feature, in which case incoming control messages need to be dispatched by calling `handle_control_message()`. The derived class must additionally override `process_device_ready()`, `process_port_ready()` and `process_port_open()` to implement the actual behaviour. The derived class has the following responsibilities:

- inform the driver about usable ports once the device is ready as signaled in `process_device_ready()`, see the wrapper `port_add()`.
- inform the driver about unusable ports, see the wrapper `port_remove()`.
- react to open/close events, see the wrapper `port_open()`.

This implementation provides no means to handle interrupts or notify guests, therefore derived classes have to provide this functionality, see `notify_queue()` and `handle_control_message()`. Similarly, all interaction with data queues has to be implemented. Memory for port structures must be managed by the implementor as well.

Use this class as a base to implement your own specific console device.

Definition at line 267 of file `virtio-console`.



## 15.404.2 Constructor & Destructor Documentation

### 15.404.2.1 Virtio\_con()

```
L4virtio::Svr::Console::Virtio_con::Virtio_con (
    unsigned max_ports,
    bool enable_multiport) [inline], [explicit]
```

Create a new multiport console device.

#### Parameters


<i>max_ports</i>	Maximum number of ports the device should be able to handle (ignored when <i>enable_multiport</i> is false).
<i>enable_multiport</i>	Enable the control queue for dynamic handling of ports.

Definition at line 293 of file [virtio-console](#).


References [L4Re::chksys\(\)](#), [L4virtio::Svr::Console::Features::console\\_multiport\(\)](#), [L4\\_EINVAL](#), [L4VIRTIO\\_ID\\_CONSOLE](#), and [L4virtio::Svr::Dev\\_features::raw](#).

Referenced by [L4virtio::Svr::Console::Device::Device\(\)](#), [L4virtio::Svr::Console::Device::Device\(\)](#), and [L4virtio::Svr::Console::Device::D](#)

Here is the call graph for this function:



Here is the caller graph for this function:



### 15.404.3 Member Function Documentation

#### 15.404.3.1 handle\_control\_message()

```
int L4virtio::Svr::Console::Virtio_con::handle_control_message () [inline]
```

Handle control message received from the driver.

##### Return values


<i>L4_EOK</i>	Message has been handled.
<i>-L4_ENODEV</i>	Control queue is not ready.
<i>-L4_EINVAL</i>	Received an unexpected control event.

This function performs the basic handling of control messages from the driver. It does all necessary work with the control queues and performs some sanity checks. All other work is deferred to the derived class, see [process\\_device\\_ready\(\)](#), [process\\_port\\_ready\(\)](#) and [process\\_port\\_open\(\)](#).

Definition at line 536 of file [virtio-console](#).

References [L4virtio::Svr::Console::Control\\_message::Device\\_ready](#), [L4virtio::Svr::Console::Control\\_message::event](#), [L4virtio::Svr::Virtqueue::finish\(\)](#), [L4virtio::Svr::Console::Control\\_message::id](#), [L4\\_EINVAL](#), [L4\\_ENODEV](#), [L4\\_EOK](#), [L4virtio::Svr::Console::Control\\_request::len](#), [L4virtio::Svr::Console::Control\\_request::msg](#), [L4virtio::Svr::Virtqueue::next\\_avail\(\)](#), [L4virtio::Svr::Console::Port::Port\\_disabled](#), [L4virtio::Svr::Console::Control\\_message::Port\\_open](#), [L4virtio::Svr::Console::Port::Port\\_op](#), [L4virtio::Svr::Console::Control\\_message::Port\\_ready](#), [process\\_device\\_ready\(\)](#), [process\\_port\\_open\(\)](#), [process\\_port\\_ready\(\)](#), [L4virtio::Virtqueue::ready\(\)](#), [L4virtio::Svr::Request\\_processor::start\(\)](#), and [L4virtio::Svr::Console::Control\\_message::value](#).

Here is the call graph for this function:



### 15.404.3.2 notify\_queue()

```
virtual void L4virtio::Svr::Console::Virtio_con::notify_queue (  
    Virtqueue * queue) [pure virtual]
```

Notify queue of available data.

#### Parameters

<i>queue</i>	<a href="#">Virtqueue</a> to notify.
--------------	--------------------------------------

This callback is called whenever data is sent to `queue`. It is the responsibility of the derived class to perform all necessary notification actions, e.g. triggering guest interrupts.

Implemented in [L4virtio::Svr::Console::Device](#).

### 15.404.3.3 port()

```
virtual Port * L4virtio::Svr::Console::Virtio_con::port (  
    unsigned port) [pure virtual]
```

Return the specified port.

#### Parameters

<i>port</i>	<a href="#">Port</a> number.
-------------	------------------------------

#### Precondition


[Port](#) number must be lower than the configured maximum number of ports.

Implemented in [L4virtio::Svr::Console::Device](#).


References [port\(\)](#).

Referenced by [check\\_queues\(\)](#), [port\(\)](#), [port\\_add\(\)](#), [port\\_name\(\)](#), [port\\_open\(\)](#), [port\\_remove\(\)](#), [process\\_port\\_ready\(\)](#), and [reset\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



#### 15.404.3.4 port\_add()

```
int L4virtio::Svr::Console::Virtio_con::port_add (
    unsigned idx) [inline]
```

Send a DEVICE\_ADD message and update the internal state.

#### Parameters

<i>idx</i>	Port that should be added.
------------	----------------------------

#### Return values

<i>L4_EOK</i>	Message has been sent.
<i>-L4_EPERM</i>	Invalid state transition.

#### Precondition


*idx* must be smaller than the configured number of ports.  
 Port must not already exist.

Definition at line 379 of file [virtio-console](#).


References [L4\\_EOK](#), [L4\\_EPERM](#), [port\(\)](#), [L4virtio::Svr::Console::Port::Port\\_added](#), [L4virtio::Svr::Console::Port::Port\\_disabled](#), and [L4virtio::Svr::Console::Port::status](#).

Referenced by [L4virtio::Svr::Console::Device::process\\_device\\_ready\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



#### 15.404.3.5 port\_name()

```
int L4virtio::Svr::Console::Virtio_con::port_name (
    unsigned idx,
    char const * name) [inline]
```

Send a PORT\_NAME message to announce the port name.

##### Parameters

<i>idx</i>	<a href="#">Port</a> that should be opened or closed.
<i>name</i>	The port name

##### Return values

<i>L4_EOK</i>	Message has been sent.
<i>-L4_EPERM</i>	Control message is not allowed in the current state.

##### Returns

Errors from [send\\_control\\_message\(\)](#)

**Precondition**


`idx` must be smaller than the configured number of ports.

`Port` must already exist.

Definition at line 455 of file `virtio-console`.

References `L4_EPERM`, `port()`, `L4virtio::Svr::Console::Port::Port_disabled`, `L4virtio::Svr::Console::Control_message::Port_name`, `send_control_message()`, and `L4virtio::Svr::Console::Port::status`.

Here is the call graph for this function:

**15.404.3.6 port\_open()**

```
int L4virtio::Svr::Console::Virtio_con::port_open (
    unsigned idx,
    bool open) [inline]
```

Send a PORT\_OPEN message and update the internal state.

**Parameters**

<code>idx</code>	<code>Port</code> that should be opened or closed.
<code>open</code>	Open or close port.

**Return values**

<code>L4_EOK</code>	Message has been sent.
<code>-L4_EPERM</code>	Invalid state transition.

**Precondition**

`idx` must be smaller than the configured number of ports.


[Port](#) must be ready when opening or open when closing.

Definition at line 428 of file [virtio-console](#).


References [L4\\_EOK](#), [L4\\_EPERM](#), [port\(\)](#), [L4virtio::Svr::Console::Port::Port\\_open](#), [L4virtio::Svr::Console::Port::Port\\_ready](#), and [L4virtio::Svr::Console::Port::status](#).

Referenced by [L4virtio::Svr::Console::Device::process\\_port\\_ready\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:

**15.404.3.7 port\_remove()**

```
int L4virtio::Svr::Console::Virtio_con::port_remove (
    unsigned idx) [inline]
```

Send a `DEVICE_REMOVE` message and update the internal state.

**Parameters**

<code>idx</code>	<a href="#">Port</a> that should be removed.
------------------	--

**Return values**

<code>L4_EOK</code>	Message has been sent.
<code>-L4_EPERM</code>	Invalid state transition.

**Precondition**

`idx` must be smaller than the configured number of ports.


`Port` must already exist.

Definition at line 403 of file [virtio-console](#).


References [L4\\_EOK](#), [L4\\_EPERM](#), [port\(\)](#), [L4virtio::Svr::Console::Port::Port\\_disabled](#), and [L4virtio::Svr::Console::Port::status](#).

Referenced by [L4virtio::Svr::Console::Device::process\\_port\\_ready\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:

**15.404.3.8 process\_device\_ready()**

```
virtual void L4virtio::Svr::Console::Virtio_con::process_device_ready (
    l4_uint16_t value) [pure virtual]
```

Callback called on DEVICE\_READY event.



**Parameters**


<i>value</i>	The value field of the control message, indicating if the initialization was successful.
--------------	--

Needs to be overridden by the derived class if the MULTIPORT feature is enabled. Control messages may be sent only after the driver has successfully initialized the device.

Implemented in [L4virtio::Svr::Console::Device](#).

Referenced by [handle\\_control\\_message\(\)](#).

Here is the caller graph for this function:

**15.404.3.9 process\_port\_open()**

```
virtual void L4virtio::Svr::Console::Virtio_con::process_port_open (
    l4_uint32_t id,
    l4_uint16_t value) [pure virtual]
```

Callback called on PORT\_OPEN event.

**Parameters**

<i>id</i>	The id field of the control message, i.e. the port number.
<i>value</i>	The value field of the control message, indicating if the port was opened or closed.

Signal that an application has opened the port. Can to be overridden by the derived class if the MULTIPORT feature is enabled.

Implemented in [L4virtio::Svr::Console::Device](#).

Referenced by [handle\\_control\\_message\(\)](#).

Here is the caller graph for this function:



### 15.404.3.10 process\_port\_ready()

```
virtual void L4virtio::Svr::Console::Virtio_con::process_port_ready (
    l4_uint32_t id,
    l4_uint16_t value) [inline], [virtual]
```

Callback called on PORT\_READY event.

#### Parameters

<i>id</i>	The id field of the control message, i.e. the port number.
<i>value</i>	The value field of the control message, indicating if the initialization was successful.

May be overridden by the derived class if the MULTIPORT feature is enabled. This default implementation just sets the status of the port according to the driver message.


Reimplemented in [L4virtio::Svr::Console::Device](#).

Definition at line 698 of file [virtio-console](#).


References [port\(\)](#), [L4virtio::Svr::Console::Port::Port\\_added](#), [L4virtio::Svr::Console::Port::Port\\_failed](#), [L4virtio::Svr::Console::Port::Port\\_ready](#), and [L4virtio::Svr::Console::Port::status](#).

Referenced by [handle\\_control\\_message\(\)](#), and [L4virtio::Svr::Console::Device::process\\_port\\_ready\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



**15.404.3.11 reset\_device()**

```
virtual void L4virtio::Svr::Console::Virtio_con::reset_device () [inline], [virtual]
```


Reset the state of the actual console device.

This callback is called at the end of `reset()`, allowing the derived class to reset internal state.

Definition at line 652 of file `virtio-console`.

Referenced by `reset()`.

Here is the caller graph for this function:

**15.404.3.12 send\_control\_message()**

```
int L4virtio::Svr::Console::Virtio_con::send_control_message (
    l4_uint32_t idx,
    l4_uint16_t event,
    l4_uint16_t value = 0,
    const char * name = 0) [inline]
```

Send control message to driver.

**Parameters**

<i>idx</i>	Port number.
<i>event</i>	Kind of control event.
<i>value</i>	Extra information for the event.
<i>name</i>	Name to be used for Port_name message

**Return values**

<i>L4_EOK</i>	Message has been sent.
<i>-L4_ENODEV</i>	Control queue is not ready.
<i>-L4_EBUSY</i>	Currently no descriptor available in the control queue.
<i>-L4_ENOMEM</i>	Client-issued descriptor too small. Device will be set to failed state.

**Precondition**

`port` must be smaller than the configured number of ports.


The convenience functions `port_add()`, `port_remove()` and `port_open()` should cover the most use cases and are the preferred way of communication with the driver. If you use this function directly, it is your responsibility to guarantee no invalid control messages are sent to the driver.

Definition at line 487 of file `virtio-console`.


References `L4virtio::Svr::Virtqueue::finish()`, `L4_EBUSY`, `L4_ENODEV`, `L4_ENOMEM`, `L4_EOK`, `L4virtio::Svr::Console::Control_request::msg`, `L4virtio::Svr::Virtqueue::next_avail()`, `L4virtio::Svr::Console::Control_message::Port_name`, `L4virtio::Virtqueue::ready()`, and `L4virtio::Svr::Request_processor::start()`.

Referenced by `port_name()`.

Here is the call graph for this function:



Here is the caller graph for this function:



The documentation for this class was generated from the following file:


- `l4/l4virtio/server/virtio-console`

## 15.405 L4virtio::Svr::Data\_buffer Struct Reference


Abstract data buffer.

```
#include <virtio>
```

Inheritance diagram for L4virtio::Svr::Data\_buffer:



Collaboration diagram for L4virtio::Svr::Data\_buffer:



## Public Member Functions

- `template<typename T>`  
`Data_buffer` (`T *p`)  
*Create buffer for object `p`.*
- `template<typename T>`  
`void set` (`T *p`)  
*Set buffer for object `p`.*
- `l4_uint32_t copy_to` (`Data_buffer *dst`, `l4_uint32_t max=UINT_MAX`)  
*Copy contents from this buffer to the destination buffer.*
- `l4_uint32_t skip` (`l4_uint32_t bytes`)  
*Skip given number of bytes in this buffer.*
- `bool done` () `const`  
*Check if there are no more bytes left in the buffer.*

## Data Fields

- `char * pos`  
*Current buffer position.*
- `l4_uint32_t left`  
*Bytes left in buffer.*

## 15.405.1 Detailed Description

Abstract data buffer.

Definition at line 306 of file [virtio](#).

## 15.405.2 Constructor & Destructor Documentation

### 15.405.2.1 Data\_buffer()

```
template<typename T>
L4virtio::Svr::Data_buffer::Data_buffer (
    T * p) [inline], [explicit]
```

Create buffer for object `p`.

## Template Parameters

<code>T</code>	Type of object (implicit)
----------------	---------------------------

## Parameters

<code>p</code>	Pointer to object.
----------------	--------------------

The buffer shall point to the start of the object `p` and the size `left` is `sizeof(T)`.

Definition at line 323 of file [virtio](#).

References [left](#), and [pos](#).

### 15.405.3 Member Function Documentation

#### 15.405.3.1 copy\_to()

```
14_uint32_t L4virtio::Svr::Data_buffer::copy_to (
    Data_buffer * dst,
    14_uint32_t max = UINT_MAX) [inline]
```

Copy contents from this buffer to the destination buffer.

##### Parameters

<i>dst</i>	Destination buffer.
<i>max</i>	(optional) Maximum number of bytes to copy.

##### Returns

the number of bytes copied.


This function copies at most `max` bytes from this to `dst`. If `max` is omitted, copies the maximum number of bytes available that fit `dst`.

Definition at line 354 of file [virtio](#).

References [left](#), and [pos](#).

Referenced by [Virtio\\_vlan\\_mangle::copy\\_pkt\(\)](#), [L4virtio::Svr::Console::Device::port\\_read\(\)](#), and [L4virtio::Svr::Console::Device::port\\_w](#)

Here is the caller graph for this function:



**15.405.3.2 done()**

```
bool L4virtio::Svr::Data_buffer::done () const [inline]
```

Check if there are no more bytes left in the buffer.

**Returns**

true if there are no more bytes left in the buffer.

Definition at line 388 of file [virtio](#).

References [left](#).

**15.405.3.3 set()**

```
template<typename T>
void L4virtio::Svr::Data_buffer::set (
    T * p) [inline]
```

Set buffer for object p.

**Template Parameters**

<i>T</i>	Type of object (implicit)
----------	---------------------------

**Parameters**

<i>p</i>	Pointer to object.
----------	--------------------

The buffer shall point to the start of the object p and the size left is sizeof(T).

Definition at line 337 of file [virtio](#).

References [left](#), and [pos](#).

**15.405.3.4 skip()**

```
l4_uint32_t L4virtio::Svr::Data_buffer::skip (
    l4_uint32_t bytes) [inline]
```

Skip given number of bytes in this buffer.

**Parameters**

<i>bytes</i>	Number of bytes that shall be skipped.
--------------	--



### Returns

The number of bytes skipped.


Try to skip the given number of bytes in this buffer, if there are less bytes left in the buffer that given then at most left bytes are skipped and the amount is returned.

Definition at line 375 of file [virtio](#).

References [left](#), and [pos](#).

Referenced by [Virtio\\_vlan\\_mangle::copy\\_pkt\(\)](#).

Here is the caller graph for this function:



The documentation for this struct was generated from the following file:

- [l4/l4virtio/server/virtio](#)

## 15.406 L4virtio::Svr::Dev\_config Class Reference

Abstraction for L4-Virtio device config memory.

```
#include <l4virtio>
```

Collaboration diagram for L4virtio::Svr::Dev\_config:



## Public Member Functions

- [Dev\\_config](#) (l4\_uint32\_t vendor, l4\_uint32\_t device, unsigned cfg\_size, l4\_uint32\_t num\_queues=0)  
*Create a L4-Virtio config data space.*
- [Dev\\_config](#) (Cfg\_cap const &cfg, l4\_addr\_t cfg\_offset, l4\_uint32\_t vendor, l4\_uint32\_t device, unsigned cfg\_size, l4\_uint32\_t num\_queues=0)  
*Setup an L4-Virtio config space in an existing data space.*
- void [set\\_device\\_notify\\_index](#) (unsigned idx)  
*Set index of interrupt that driver should trigger for config notifications.*
- l4\_uint32\_t [num\\_queues](#) () const  
*Return the number of queues currently usable.*
- l4\_uint32\_t [guest\\_features](#) (unsigned idx) const  
*Return a specific set of guest features.*
- l4\_uint32\_t [negotiated\\_features](#) (unsigned idx) const  
*Compute a specific set of negotiated features.*
- Status [status](#) () const  
*Get current device status (trusted).*
- l4\_uint32\_t [get\\_cmd](#) () const  
*Get the value from the cmd register.*
- void [reset\\_cmd](#) ()  
*Reset the cmd register after execution of a command.*
- void [set\\_status](#) (Status status)  
*Set device status register.*
- void [add\\_irq\\_status](#) (l4\_uint32\_t status)

- Adds irq status bit.*
- void [set\\_device\\_needs\\_reset](#) ()  
*Set DEVICE\_NEEDS\_RESET bit in device status register.*
- bool [change\\_queue\\_config](#) (l4\_uint32\_t num\_queues)  
*Setup new queue configuration.*
- [l4virtio\\_config\\_queue\\_t](#) volatile const \* [qconfig](#) (unsigned index) const  
*Get queue read-only config data for queue with the given index.*
- void [reset\\_hdr](#) (bool inc\_generation=false) const  
*Reset the config header to the initial contents.*
- bool [reset\\_queue](#) (unsigned index, unsigned num\_max, bool inc\_generation=false, unsigned device\_notify↵\_index=0) const  
*Reset queue config for the given queue.*
- [l4virtio\\_config\\_hdr\\_t](#) const volatile \* [hdr](#) () const  
*Get a read-only pointer to the config header.*
- [L4::Cap](#)< [L4Re::Dataspace](#) > [ds](#) () const  
*Get data-space capability for the shared config data space.*
- [l4\\_addr\\_t](#) [ds\\_offset](#) () const  
*Return the offset into the config dataspace where the device configuration starts.*

## 15.406.1 Detailed Description

Abstraction for L4-Virtio device config memory.

Virtio defines a device configuration mechanism, L4-Virtio implements this mechanism based on shared memory a [set\\_status\(\)](#) and a [config\\_queue\(\)](#) call. This class provides an abstraction for L4-Virtio host implementations to establish such a shared memory data space and providing the necessary contents and access functions.

Definition at line 52 of file [l4virtio](#).

## 15.406.2 Constructor & Destructor Documentation

### 15.406.2.1 Dev\_config() [1/2]

```
L4virtio::Svr::Dev_config::Dev_config (
    l4_uint32_t vendor,
    l4_uint32_t device,
    unsigned cfg_size,
    l4_uint32_t num_queues = 0) [inline]
```

Create a L4-Virtio config data space.

#### Parameters


<i>vendor</i>	The vendor ID to store in config header.
<i>device</i>	The device ID to store in config header.
<i>cfg_size</i>	The size of the device-specific config data in bytes.
<i>num_queues</i>	The number of queues provided by the device.

This constructor allocates a data space used for L4-virtio config attaches the data space to the local address space and writes the initial contents to the config header.

Definition at line 112 of file [l4virtio](#).

References [L4Re::chkcap\(\)](#), [L4Re::chksys\(\)](#), [L4Re::Env::env\(\)](#), [L4\\_PAGESIZE](#), [L4Re::Util::make\\_shared\\_cap\(\)](#), and [num\\_queues\(\)](#).

Here is the call graph for this function:



### 15.406.2.2 Dev\_config() [2/2]

```

L4virtio::Svr::Dev_config::Dev_config (
    Cfg_cap const & cfg,
    l4_addr_t cfg_offset,
    l4_uint32_t vendor,
    l4_uint32_t device,
    unsigned cfg_size,
    l4_uint32_t num_queues = 0) [inline]

```

Setup an L4-Virtio config space in an existing data space.


#### Parameters

<i>cfg</i>	Dataspace that should hold the L4-Virtio configuration.
<i>cfg_offset</i>	Offset into the dataspace where the configuration starts.
<i>vendor</i>	The vendor ID to store in config header.
<i>device</i>	The device ID to store in config header.
<i>cfg_size</i>	The size of the device-specific config data in bytes.
<i>num_queues</i>	The number of queues provided by the device.

Definition at line 146 of file [l4virtio](#).

References [L4\\_PAGESIZE](#), and [num\\_queues\(\)](#).

Here is the call graph for this function:



### 15.406.3 Member Function Documentation

#### 15.406.3.1 `add_irq_status()`

```
void L4virtio::Svr::Dev_config::add_irq_status (
    14_uint32_t status) [inline]
```

Adds irq status bit.

##### Parameters


<i>status</i>	The value to add to the irq status register.
---------------	--

This function adds the status bit to the irq status register.

Definition at line 274 of file [l4virtio](#).

References [hdr\(\)](#), and [status\(\)](#).

Here is the call graph for this function:



### 15.406.3.2 `change_queue_config()`

```
bool L4virtio::Svr::Dev_config::change_queue_config (
    l4_uint32_t num_queues) [inline]
```

Setup new queue configuration.


#### Parameters

<code>num_queues</code>	The number of queues provided by the device.
-------------------------	--

Definition at line 295 of file [l4virtio](#).

References [L4\\_PAGESIZE](#), [num\\_queues\(\)](#), and [reset\\_hdr\(\)](#).

Here is the call graph for this function:



### 15.406.3.3 `ds()`

```
L4::Cap< L4Re::Dataspace > L4virtio::Svr::Dev_config::ds () const [inline]
```

Get data-space capability for the shared config data space.

#### Returns

Capability for the shared config data space.

Definition at line 388 of file [l4virtio](#).

#### 15.406.3.4 get\_cmd()

```
l4_uint32_t L4virtio::Svr::Dev_config::get_cmd () const [inline]
```


Get the value from the `cmd` register.

Note, the most significant eight bits are the command (0 is nothing to do). The upper eight bit are reset to zero after the command was handled.

Definition at line 239 of file [l4virtio](#).

References [hdr\(\)](#).

Here is the call graph for this function:



#### 15.406.3.5 guest\_features()

```
l4_uint32_t L4virtio::Svr::Dev_config::guest_features (
    unsigned idx) const [inline]
```

Return a specific set of guest features.

##### Parameters

<i>idx</i>	Index into the guest features array.
------------	--------------------------------------

##### Return values

<i>The</i>	selected set of guest features.
------------	---------------------------------

This function returns a specific 32bit set of features enabled by the guest/driver. `idx` is the index in the guest features array, resp. the 32 bit set to return.

Definition at line 207 of file [l4virtio](#).

### 15.406.3.6 `hdr()`

```
l4virtio_config_hdr_t const volatile * L4virtio::Svr::Dev_config::hdr () const [inline]
```

Get a read-only pointer to the config header.


#### Returns

Read-only pointer to the shared config header.

Definition at line 381 of file `l4virtio`.

Referenced by `add_irq_status()`, `get_cmd()`, `reset_cmd()`, `set_device_needs_reset()`, and `set_status()`.

Here is the caller graph for this function:



### 15.406.3.7 `negotiated_features()`

```
l4_uint32_t L4virtio::Svr::Dev_config::negotiated_features (
    unsigned idx) const [inline]
```

Compute a specific set of negotiated features.



### Parameters

<i>idx</i>	Index into the guest/host features array.
------------	---

### Return values

<i>The</i>	selected set of negotiated features.
------------	--------------------------------------

This function returns a specific 32-bit set of features negotiated by the guest/driver and host/device. *idx* is the index in the guest/host features array, resp. the 32-bit set to return.

Definition at line 221 of file [l4virtio](#).

### 15.406.3.8 qconfig()

```
l4virtio_config_queue_t volatile const * L4virtio::Svr::Dev_config::qconfig (
    unsigned index) const [inline]
```

Get queue read-only config data for queue with the given *index*.

### Parameters

<i>index</i>	The index of the queue.
--------------	-------------------------

### Returns

Read-only pointer to the config of the queue with the given *index*, or NULL if *index* is out of range.

Definition at line 312 of file [l4virtio](#).

References [L4\\_UNLIKELY](#).

Referenced by [reset\\_queue\(\)](#).

Here is the caller graph for this function:



### 15.406.3.9 reset\_cmd()

```
void L4virtio::Svr::Dev_config::reset_cmd () [inline]
```


Reset the `cmd` register after execution of a command.

This function resets the `cmd` register in order for the client to detect that the command was executed by the device.

Definition at line 250 of file [l4virtio](#).

References [hdr\(\)](#).

Here is the call graph for this function:



### 15.406.3.10 reset\_queue()

```
bool L4virtio::Svr::Dev_config::reset_queue (
    unsigned index,
    unsigned num_max,
    bool inc_generation = false,
    unsigned device_notify_index = 0) const [inline]
```

Reset queue config for the given queue.

#### Parameters

<i>index</i>	The index of the queue to reset.
<i>num_max</i>	The maximum number of descriptors supported by this queue.
<i>inc_generation</i>	The config generation will be incremented when this is true.
<i>device_notify_index</i>	<a href="#">Device</a> notification Irq index for this queue. See <a href="#">Device_t::device_notify_irq(unsigned)</a> .


### Returns

true on success, or false when *index* is out of range.

Definition at line 356 of file [l4virtio](#).

References [l4virtio\\_config\\_queue\\_t::device\\_notify\\_index](#), [L4\\_UNLIKELY](#), [l4virtio\\_config\\_queue\\_t::num](#), [l4virtio\\_config\\_queue\\_t::num\\_qconfig\(\)](#), and [l4virtio\\_config\\_queue\\_t::ready](#).

Here is the call graph for this function:



#### 15.406.3.11 set\_device\_needs\_reset()

```
void L4virtio::Svr::Dev_config::set_device_needs_reset () [inline]
```


Set `DEVICE_NEEDS_RESET` bit in device status register.

This function sets the internal status register and also the status register in the shared memory to `DEVICE_NEEDS_RESET`.

Definition at line 285 of file [l4virtio](#).

References [hdr\(\)](#).

Here is the call graph for this function:



#### 15.406.3.12 set\_device\_notify\_index()

```
void L4virtio::Svr::Dev_config::set_device_notify_index (
    unsigned idx) [inline]
```

Set index of interrupt that driver should trigger for config notifications.

See [Device\\_t::device\\_notify\\_irq\(unsigned\)](#).

Definition at line 187 of file [l4virtio](#).

#### 15.406.3.13 set\_status()

```
void L4virtio::Svr::Dev_config::set_status (
    Status status) [inline]
```

Set device status register.

##### Parameters


<i>status</i>	The new value for the device status register.
---------------	---

This function sets the internal status register and also the status register in the shared memory to *status*.

Definition at line 262 of file [l4virtio](#).

References [hdr\(\)](#), and [status\(\)](#).

Here is the call graph for this function:



### 15.406.3.14 status()

```
Status L4virtio::Svr::Dev_config::status () const [inline]
```

Get current device status (trusted).

#### Returns


Current device status register (trusted).

The status returned by this function is value stored internally and cannot be written by the guest (i.e., the value can be taken as trusted.)

Definition at line 231 of file [l4virtio](#).

Referenced by [add\\_irq\\_status\(\)](#), and [set\\_status\(\)](#).

Here is the caller graph for this function:



The documentation for this class was generated from the following file:


- `l4/l4virtio/server/l4virtio`

## 15.407 L4virtio::Svr::Dev\_features Struct Reference

Type for device feature bitmap.

```
#include <virtio>
```

Inheritance diagram for L4virtio::Svr::Dev\_features:



Collaboration diagram for L4virtio::Svr::Dev\_features:



## Public Member Functions

- **Dev\_features** ([l4\\_uint32\\_t](#) v)  
*Make Features from a raw bitmap.*

## Data Fields

- [l4\\_uint32\\_t](#) raw  
*The raw value of the features bitmap.*
- typedef [cxx::Bitfield](#)< decltype(raw), 28, 28 > **ring\_indirect\_desc\_bfm\_t**  
*Type to access the [ring\\_indirect\\_desc](#) bits (28 to 28) of raw.*
- constexpr [ring\\_indirect\\_desc\\_bfm\\_t::Val](#) **ring\_indirect\_desc** () const  
*Get the [ring\\_indirect\\_desc](#) bits (28 to 28) of raw.*
- constexpr [ring\\_indirect\\_desc\\_bfm\\_t::Ref](#) **ring\_indirect\_desc** ()  
*Get a reference to the [ring\\_indirect\\_desc](#) bits (28 to 28) of raw.*
- typedef [cxx::Bitfield](#)< decltype(raw), 29, 29 > **ring\_event\_idx\_bfm\_t**  
*Type to access the [ring\\_event\\_idx](#) bits (29 to 29) of raw.*
- constexpr [ring\\_event\\_idx\\_bfm\\_t::Val](#) **ring\_event\_idx** () const  
*Get the [ring\\_event\\_idx](#) bits (29 to 29) of raw.*
- constexpr [ring\\_event\\_idx\\_bfm\\_t::Ref](#) **ring\_event\_idx** ()  
*Get a reference to the [ring\\_event\\_idx](#) bits (29 to 29) of raw.*

### 15.407.1 Detailed Description

Type for device feature bitmap.

Definition at line 66 of file [virtio](#).

The documentation for this struct was generated from the following file:

- l4/l4virtio/server/virtio

## 15.408 L4virtio::Svr::Dev\_status Struct Reference

Type of the device status register.

```
#include <virtio>
```



Collaboration diagram for L4virtio::Svr::Dev\_status:

L4virtio::Svr::Dev_status
+ raw
+ Dev_status()
+ running()
* acked_bfm_t
* acked()
* acked()
* driver_bfm_t
* driver()
* driver()
* driver_ok_bfm_t
* driver_ok()
* driver_ok()
* features_ok_bfm_t
* features_ok()
* features_ok()
* fail_state_bfm_t
* fail_state()
* fail_state()
* device_needs_reset_bfm_t
* device_needs_reset()
* device_needs_reset()
* failed_bfm_t
* failed()
* failed()

## Public Member Functions

- **Dev\_status** ([l4\\_uint32\\_t](#) v)  
*Make Status from raw value.*
- bool [running](#) () const  
*Check if the device is in running state.*

## Data Fields

- unsigned char **raw**  
*Raw value of the VIRTIO device status register.*
- typedef `cxx::Bitfield< decltype(raw), 0, 0 >` **acked\_bfm\_t**  
*Type to access the `acked` bits (0 to 0) of `raw`.*
- constexpr `acked_bfm_t::Val` **acked** () const  
*Get the `acked` bits (0 to 0) of `raw`.*
- constexpr `acked_bfm_t::Ref` **acked** ()  
*Get a reference to the `acked` bits (0 to 0) of `raw`.*
- typedef `cxx::Bitfield< decltype(raw), 1, 1 >` **driver\_bfm\_t**  
*Type to access the `driver` bits (1 to 1) of `raw`.*
- constexpr `driver_bfm_t::Val` **driver** () const  
*Get the `driver` bits (1 to 1) of `raw`.*
- constexpr `driver_bfm_t::Ref` **driver** ()  
*Get a reference to the `driver` bits (1 to 1) of `raw`.*
- typedef `cxx::Bitfield< decltype(raw), 2, 2 >` **driver\_ok\_bfm\_t**  
*Type to access the `driver_ok` bits (2 to 2) of `raw`.*
- constexpr `driver_ok_bfm_t::Val` **driver\_ok** () const  
*Get the `driver_ok` bits (2 to 2) of `raw`.*
- constexpr `driver_ok_bfm_t::Ref` **driver\_ok** ()  
*Get a reference to the `driver_ok` bits (2 to 2) of `raw`.*
- typedef `cxx::Bitfield< decltype(raw), 3, 3 >` **features\_ok\_bfm\_t**  
*Type to access the `features_ok` bits (3 to 3) of `raw`.*
- constexpr `features_ok_bfm_t::Val` **features\_ok** () const  
*Get the `features_ok` bits (3 to 3) of `raw`.*
- constexpr `features_ok_bfm_t::Ref` **features\_ok** ()  
*Get a reference to the `features_ok` bits (3 to 3) of `raw`.*
- typedef `cxx::Bitfield< decltype(raw), 6, 7 >` **fail\_state\_bfm\_t**  
*Type to access the `fail_state` bits (6 to 7) of `raw`.*
- constexpr `fail_state_bfm_t::Val` **fail\_state** () const  
*Get the `fail_state` bits (6 to 7) of `raw`.*
- constexpr `fail_state_bfm_t::Ref` **fail\_state** ()  
*Get a reference to the `fail_state` bits (6 to 7) of `raw`.*
- typedef `cxx::Bitfield< decltype(raw), 6, 6 >` **device\_needs\_reset\_bfm\_t**  
*Type to access the `device_needs_reset` bits (6 to 6) of `raw`.*
- constexpr `device_needs_reset_bfm_t::Val` **device\_needs\_reset** () const  
*Get the `device_needs_reset` bits (6 to 6) of `raw`.*
- constexpr `device_needs_reset_bfm_t::Ref` **device\_needs\_reset** ()  
*Get a reference to the `device_needs_reset` bits (6 to 6) of `raw`.*
- typedef `cxx::Bitfield< decltype(raw), 7, 7 >` **failed\_bfm\_t**  
*Type to access the `failed` bits (7 to 7) of `raw`.*
- constexpr `failed_bfm_t::Val` **failed** () const  
*Get the `failed` bits (7 to 7) of `raw`.*
- constexpr `failed_bfm_t::Ref` **failed** ()  
*Get a reference to the `failed` bits (7 to 7) of `raw`.*

### 15.408.1 Detailed Description

Type of the device status register.

Definition at line 32 of file [virtio](#).

### 15.408.2 Member Function Documentation

#### 15.408.2.1 running()

```
bool L4virtio::Svr::Dev_status::running () const [inline]
```

Check if the device is in running state.

##### Returns

true if the device is in running state.

The device is in running state when [acked\(\)](#), [driver\(\)](#), [features\\_ok\(\)](#), and [driver\\_ok\(\)](#) return true, and [device\\_needs\\_reset\(\)](#) and [failed\(\)](#) return false.

Definition at line 57 of file [virtio](#).

References [raw](#).


The documentation for this struct was generated from the following file:

- l4/l4virtio/server/virtio

## 15.409 L4virtio::Svr::Device\_t< DATA > Class Template Reference

Server-side L4-VIRTIO device stub.

```
#include <l4virtio>
```



Collaboration diagram for L4virtio::Svr::Device\_t< DATA >:

L4virtio::Svr::Device _t< DATA >
# _mem_info
+ reset() + check_features() + check_queues() + reconfig_queue() + cfg_changed() + register_single_driver_irq() + trigger_driver_config_irq() + device_notify_irq() + register_driver_irq() + device_notify_irq() and 10 more...

## Public Member Functions

- virtual void **reset** ()=0  
*reset callback, called for doing a device reset*
- virtual bool **check\_features** ()  
*callback for checking the subset of accepted features*
- virtual bool **check\_queues** ()=0  
*callback for checking if the queues at DRIVER\_OK transition*
- virtual int **reconfig\_queue** (unsigned idx)=0  
*callback for client queue-config request*
- virtual void **cfg\_changed** (unsigned)  
*callback for client device configuration changes*
- virtual void **register\_single\_driver\_irq** ()  
*callback for registering a single guest IRQ for all queues (old-style)*
- virtual void **trigger\_driver\_config\_irq** ()=0  
*callback for triggering configuration change notification IRQ*
- virtual [L4::Cap< L4::Irq >](#) **device\_notify\_irq** () const  
*callback to gather the device notification IRQ (old-style)*
- virtual void **register\_driver\_irq** (unsigned idx)  
*Callback for registering an notification IRQ (multi IRQ).*
- virtual [L4::Cap< L4::Irq >](#) **device\_notify\_irq** (unsigned idx)  
*Callback to gather the device notification IRQ (multi IRQ).*

- virtual unsigned **num\_events\_supported** () const  
*Return the highest notification index supported.*
- **Device\_t** (**Dev\_config** \*dev\_config)  
*Make a device for the given config.*
- **Mem\_list** const \* **mem\_info** () const  
*Get the memory region list used for this device.*
- void **reset\_queue\_config** (unsigned idx, unsigned num\_max, bool inc\_generation=false, unsigned device\_notify\_index=0)  
*Trigger reset for the configuration space for queue idx.*
- void **init\_mem\_info** (unsigned num)  
*Initialize the memory region list to the given maximum.*
- void **device\_error** ()  
*Transition device into DEVICE\_NEEDS\_RESET state.*
- bool **setup\_queue** (Virtqueue \*q, unsigned qn, unsigned num\_max)  
*Enable/disable the specified queue.*
- bool **handle\_mem\_cmd\_write** ()  
*Check for a value in the cmd register and handle a write.*
- void **enable\_trusted\_ds\_validation** ()  
*Enable trusted dataspace validation.*
- void **add\_trusted\_dataspaces** (std::shared\_ptr< Ds\_vector const > ds)  
*Provide a list of trusted dataspaces that can be used for validation.*

## Protected Attributes

- **Mem\_list \_mem\_info**  
*Memory region list.*

## 15.409.1 Detailed Description

```
template<typename DATA>
class L4virtio::Svr::Device_t< DATA >
```

Server-side L4-VIRTIO device stub.

This stub supports new-style multi-event registration (using `get_device_config()`, `bind()` and `get_device_notification_irq()`).

Definition at line 814 of file [l4virtio](#).

## 15.409.2 Member Function Documentation

### 15.409.2.1 add\_trusted\_dataspaces()

```
template<typename DATA>
void L4virtio::Svr::Device_t< DATA >::add_trusted_dataspaces (
    std::shared_ptr< Ds_vector const > ds) [inline]
```

Provide a list of trusted dataspaces that can be used for validation.

#### Parameters

<i>ds</i>	list of trusted dataspaces.
-----------	-----------------------------

Definition at line 1217 of file [l4virtio](#).

### 15.409.2.2 device\_error()

```
template<typename DATA>
void L4virtio::Svr::Device_t< DATA >::device_error () [inline]
```


Transition device into DEVICE\_NEEDS\_RESET state.

This function does a full reset, sets the DEVICE\_NEEDS\_RESET bit in the device status register, triggering a guest config IRQ if necessary. The driver still needs to perform its own reset and initialization sequence.

Definition at line 1043 of file [l4virtio](#).

Referenced by [Virtio\\_switch::handle\\_l4virtio\\_port\\_tx\(\)](#).

Here is the caller graph for this function:



### 15.409.2.3 device\_notify\_irq()

```
template<typename DATA>
virtual L4::Cap< L4::Irq > L4virtio::Svr::Device_t< DATA >::device_notify_irq (
    unsigned idx) [inline], [virtual]
```

Callback to gather the device notification IRQ (multi IRQ).

The default implementation maps to the implementation for single IRQ notification points.

Definition at line 887 of file [l4virtio](#).

#### 15.409.2.4 `handle_mem_cmd_write()`

```
template<typename DATA>
bool L4virtio::Svr::Device_t< DATA >::handle_mem_cmd_write () [inline]
```

Check for a value in the `cmd` register and handle a write.

This function checks for a value in the `cmd` register and executes the command if there is any, or returns false if there was no command.

Execution of the command is signaled by a zero in the `cmd` register.

Definition at line 1173 of file [l4virtio](#).

#### 15.409.2.5 `init_mem_info()`

```
template<typename DATA>
void L4virtio::Svr::Device_t< DATA >::init_mem_info (
    unsigned num) [inline]
```

Initialize the memory region list to the given maximum.

##### Parameters

<i>num</i>	Maximum number of memory regions that can be managed.
------------	---

Definition at line 1031 of file [l4virtio](#).

#### 15.409.2.6 `register_driver_irq()`

```
template<typename DATA>
virtual void L4virtio::Svr::Device_t< DATA >::register_driver_irq (
    unsigned idx) [inline], [virtual]
```

Callback for registering an notification IRQ (multi IRQ).

The default implementation maps to the implementation for single IRQ notification points.

Definition at line 873 of file [l4virtio](#).



### 15.409.2.7 reset\_queue\_config()

```
template<typename DATA>
void L4virtio::Svr::Device_t< DATA >::reset_queue_config (
    unsigned idx,
    unsigned num_max,
    bool inc_generation = false,
    unsigned device_notify_index = 0) [inline]
```

Trigger reset for the configuration space for queue *idx*.

#### Parameters

<i>idx</i>	The queue index to reset.
<i>num_max</i>	Maximum number of entries in this queue.
<i>inc_generation</i>	The config generation will be incremented when this is true.
<i>device_notify_index</i>	<a href="#">Device</a> notification Irq index for this queue. See <a href="#">device_notify_irq(unsigned)</a> .

This function resets the driver-readable configuration space for the queue with the given index. The queue configuration is reset to all 0, and the maximum number of entries in the queue is set to *num\_max*.

Definition at line 1019 of file [l4virtio](#).

### 15.409.2.8 setup\_queue()

```
template<typename DATA>
bool L4virtio::Svr::Device_t< DATA >::setup_queue (
    Virtqueue * q,
    unsigned qn,
    unsigned num_max) [inline]
```

Enable/disable the specified queue.

#### Parameters

<i>q</i>	Pointer to the ring that represents the virtqueue internally.
<i>qn</i>	Index of the queue.
<i>num_max</i>	Maximum number of supported entries in this queue.

#### Returns

true for success.

- This function calculates the parameters of the virtqueue from the clients configuration space values, checks the accessibility of the queue data structures and initializes *q* to ready state when all checks succeeded.

Definition at line 1066 of file [l4virtio](#).

The documentation for this class was generated from the following file:


- [l4/l4virtio/server/l4virtio](#)

## 15.410 L4virtio::Svr::Driver\_mem\_list\_t< DATA > Class Template Reference


List of driver memory regions assigned to a single L4-VIRTIO transport instance.

```
#include <l4virtio>
```

Inheritance diagram for L4virtio::Svr::Driver\_mem\_list\_t< DATA >:



Collaboration diagram for L4virtio::Svr::Driver\_mem\_list\_t< DATA >:



## Public Types

- typedef [L4Re::Util::Unique\\_cap](#)< [L4Re::Dataspace](#) > **Ds\_cap**  
type for storing a data-space capability internally

## Public Member Functions

- **Driver\_mem\_list\_t** ()  
Make an empty, zero capacity list.
- void **init** (unsigned max)  
Make a fresh list with capacity max.
- bool **full** () const
- Mem\_region const \* **add** (l4\_uint64\_t drv\_base, l4\_umword\_t size, l4\_addr\_t offset, [Ds\\_cap](#) &&ds)  
Add a new region to the list.
- void **remove** (Mem\_region const \*r)  
Remove the given region from the list.
- Mem\_region \* **find** (l4\_uint64\_t base, l4\_umword\_t size) const  
Find memory region containing the given driver address region.
- void **load\_desc** ([Virtqueue::Desc](#) const &desc, [Request\\_processor](#) const \*p, [Virtqueue::Desc](#) const \*\*table) const  
Default implementation for loading an indirect descriptor.
- void **load\_desc** ([Virtqueue::Desc](#) const &desc, [Request\\_processor](#) const \*p, Mem\_region const \*\*data) const  
Default implementation returning the Driver\_mem\_region.
- template<typename ARG>  
void **load\_desc** ([Virtqueue::Desc](#) const &desc, [Request\\_processor](#) const \*p, ARG \*data) const  
Default implementation returning generic information.

### 15.410.1 Detailed Description

```
template<typename DATA>
class L4virtio::Svr::Driver_mem_list_t< DATA >
```

List of driver memory regions assigned to a single L4-VIRTIO transport instance.

#### Note

The regions added to this list *must* never overlap.

Definition at line 642 of file [l4virtio](#).

### 15.410.2 Member Function Documentation

#### 15.410.2.1 add()

```
template<typename DATA>
Mem_region const * L4virtio::Svr::Driver_mem_list_t< DATA >::add (
    l4_uint64_t drv_base,
    l4_umword_t size,
    l4_addr_t offset,
    Ds_cap && ds) [inline]
```

Add a new region to the list.

#### Parameters

<i>drv_base</i>	Driver base address of the region.
<i>size</i>	Size of the region in bytes.
<i>offset</i>	Offset within the data space attached to <i>drv_base</i> .
<i>ds</i>	Data space backing the driver memory.

#### Returns

A pointer to the new region.

Definition at line 682 of file [l4virtio](#).

### 15.410.2.2 find()

```
template<typename DATA>
Mem_region * L4virtio::Svr::Driver_mem_list_t< DATA >::find (
    l4_uint64_t base,
    l4_umword_t size) const [inline]
```

Find memory region containing the given driver address region.

#### Parameters

<i>base</i>	Driver base address.
<i>size</i>	Size of the region.


#### Returns

Pointer to the region containing the given region, NULL if none is found.

Definition at line 716 of file [l4virtio](#).

Referenced by [L4virtio::Svr::Driver\\_mem\\_list\\_t< No\\_custom\\_data >::load\\_desc\(\)](#), [L4virtio::Svr::Driver\\_mem\\_list\\_t< No\\_custom\\_data >::load\\_desc\(\)](#) and [L4virtio::Svr::Driver\\_mem\\_list\\_t< No\\_custom\\_data >::load\\_desc\(\)](#).

Here is the caller graph for this function:



### 15.410.2.3 full()

```
template<typename DATA>
bool L4virtio::Svr::Driver_mem_list_t< DATA >::full () const [inline]
```

**Returns**

True if the remaining capacity is 0.

Definition at line 671 of file [l4virtio](#).

Referenced by [L4virtio::Svr::Driver\\_mem\\_list\\_t< No\\_custom\\_data >::add\(\)](#).

Here is the caller graph for this function:

**15.410.2.4 init()**

```
template<typename DATA>
void L4virtio::Svr::Driver_mem_list_t< DATA >::init (
    unsigned max) [inline]
```

Make a fresh list with capacity *max*.

**Parameters**

<i>max</i>	The capacity of this vector.
------------	------------------------------

Definition at line 663 of file [l4virtio](#).

**15.410.2.5 load\_desc() [1/3]**

```
template<typename DATA>
template<typename ARG>
void L4virtio::Svr::Driver_mem_list_t< DATA >::load_desc (
    Virtqueue::Desc const & desc,
    Request_processor const * p,
    ARG * data) const [inline]
```

Default implementation returning generic information.

**Template Parameters**

<i>ARG</i>	Abstract argument type used with <a href="#">Request_processor::start()</a> and <a href="#">Request_processor::next()</a> to deliver the result of loading a descriptor. This type must provide a constructor taking three arguments: (1) pointer to a <a href="#">Driver_mem_region</a> , (2) the <a href="#">Virtqueue::Desc</a> descriptor, and (3) a pointer to the calling <a href="#">Request_processor</a> .
------------	---

### Parameters

	<i>desc</i>	The descriptor to load
	<i>p</i>	The request processor calling us
out	<i>data</i>	Shall be assigned to ARG(mem, desc, p)

### Exceptions

<a href="#">Bad_descriptor</a>	The descriptor address could not be translated.
--------------------------------	---

Definition at line 777 of file [l4virtio](#).

#### 15.410.2.6 load\_desc() [2/3]

```
template<typename DATA>
void L4virtio::Svr::Driver_mem_list_t< DATA >::load_desc (
    Virtqueue::Desc const & desc,
    Request_processor const * p,
    Mem_region const ** data) const [inline]
```

Default implementation returning the [Driver\\_mem\\_region](#).

### Parameters

	<i>desc</i>	The descriptor to load
	<i>p</i>	The request processor calling us
out	<i>data</i>	Shall be set to a pointer to the <a href="#">Driver_mem_region</a> that covers the descriptor.

### Exceptions

<a href="#">Bad_descriptor</a>	The descriptor address could not be translated.
--------------------------------	---

Definition at line 750 of file [l4virtio](#).

#### 15.410.2.7 load\_desc() [3/3]

```
template<typename DATA>
void L4virtio::Svr::Driver_mem_list_t< DATA >::load_desc (
    Virtqueue::Desc const & desc,
```

```
Request_processor const * p,
Virtqueue::Desc const ** table) const [inline]
```

Default implementation for loading an indirect descriptor.

#### Parameters

	<i>desc</i>	The descriptor to load
	<i>p</i>	The request processor calling us
out	<i>table</i>	Shall be set to the loaded descriptor table

#### Exceptions

<a href="#"><i>Bad_descriptor</i></a>	The descriptor address could not be translated.
---------------------------------------	---

Definition at line 730 of file [l4virtio](#).

#### 15.410.2.8 remove()

```
template<typename DATA>
void L4virtio::Svr::Driver_mem_list_t< DATA >::remove (
    Mem_region const * r) [inline]
```

Remove the given region from the list.

#### Parameters

<i>r</i>	The region to remove (result from <a href="#">add()</a> , or <a href="#">find()</a> ).
----------	--

Definition at line 696 of file [l4virtio](#).

The documentation for this class was generated from the following file:

- [l4/l4virtio/server/l4virtio](#)


## 15.411 L4virtio::Svr::Driver\_mem\_region\_t< DATA > Class Template Reference

Region of driver memory, that shall be managed locally.


```
#include <l4virtio>
```



Inheritance diagram for L4virtio::Svr::Driver\_mem\_region\_t< DATA >:



Collaboration diagram for L4virtio::Svr::Driver\_mem\_region\_t< DATA >:



## Public Member Functions

- **Driver\_mem\_region\_t ()**  
*Make default empty memory region.*
- **Driver\_mem\_region\_t (l4\_uint64\_t drv\_base, l4\_umword\_t size, l4\_addr\_t offset, Ds\_cap &&ds)**  
*Make a local memory region for the given driver values.*
- bool **is\_writable ()** const
- Flags **flags ()** const
- bool **empty ()** const
- **l4\_uint64\_t drv\_base ()** const
- **l4\_addr\_t local\_base ()** const
- **l4\_umword\_t size ()** const
- **l4\_addr\_t ds\_offset ()** const
- **L4::Cap< L4Re::Dataspace > ds ()** const
- bool **contains (l4\_uint64\_t base, l4\_umword\_t size)** const  
*Test if the given driver address range is within this region.*
- template<typename T>  
**T \* local (Ptr< T > p)** const  
*Get the local address for driver address p.*

### 15.411.1 Detailed Description

```
template<typename DATA>
class L4virtio::Svr::Driver_mem_region_t< DATA >
```

Region of driver memory, that shall be managed locally.

#### Template Parameters

<i>DATA</i>	Class defining additional information
-------------	---------------------------------------

Definition at line 463 of file [l4virtio](#).

### 15.411.2 Constructor & Destructor Documentation

#### 15.411.2.1 Driver\_mem\_region\_t()

```
template<typename DATA>
L4virtio::Svr::Driver_mem_region_t< DATA >::Driver_mem_region_t (
    l4_uint64_t drv_base,
    l4_umword_t size,
    l4_addr_t offset,
    Ds_cap && ds) [inline]
```

Make a local memory region for the given driver values.

#### Parameters

<i>drv_base</i>	Base address of the memory region used by the driver.
<i>size</i>	Size of the memory region.
<i>offset</i>	Offset within the data space that is mapped to <i>drv_base</i> within the driver.
<i>ds</i>	Data space capability backing the memory.

This constructor attaches the region of given data space to the local address space and stores the corresponding data for later reference.

Definition at line 511 of file [l4virtio](#).

### 15.411.3 Member Function Documentation

#### 15.411.3.1 contains()

```
template<typename DATA>
bool L4virtio::Svr::Driver_mem_region_t< DATA >::contains (
    l4_uint64_t base,
    l4_umword_t size) const [inline]
```

Test if the given driver address range is within this region.

**Parameters**

<i>base</i>	The driver base address.
<i>size</i>	The size of the region to lookup.

**Returns**

true if the given driver address region is contained in this region, false else.

Definition at line 605 of file [l4virtio](#).

**15.411.3.2 drv\_base()**

```
template<typename DATA>
l4_uint64_t L4virtio::Svr::Driver_mem_region_t< DATA >::drv_base () const [inline]
```

**Returns**

The base address used by the driver.

Definition at line 584 of file [l4virtio](#).

**15.411.3.3 ds()**

```
template<typename DATA>
L4::Cap< L4Re::Dataspace > L4virtio::Svr::Driver_mem_region_t< DATA >::ds () const [inline]
```

**Returns**

The data space capability for this region.

Definition at line 596 of file [l4virtio](#).

**15.411.3.4 ds\_offset()**

```
template<typename DATA>
l4_addr_t L4virtio::Svr::Driver_mem_region_t< DATA >::ds_offset () const [inline]
```

**Returns**

The offset within the data space.

Definition at line 593 of file [l4virtio](#).

### 15.411.3.5 empty()

```
template<typename DATA>
bool L4virtio::Svr::Driver_mem_region_t< DATA >::empty () const [inline]
```

#### Returns

True if the region is empty (size == 0), false otherwise.

Definition at line 580 of file [l4virtio](#).

### 15.411.3.6 flags()

```
template<typename DATA>
Flags L4virtio::Svr::Driver_mem_region_t< DATA >::flags () const [inline]
```

#### Returns

The flags for this region.

Definition at line 577 of file [l4virtio](#).

### 15.411.3.7 is\_writable()

```
template<typename DATA>
bool L4virtio::Svr::Driver_mem_region_t< DATA >::is_writable () const [inline]
```

#### Returns

True if the region is writable, false otherwise.

Definition at line 574 of file [l4virtio](#).

### 15.411.3.8 local()

```
template<typename DATA>
template<typename T>
T * L4virtio::Svr::Driver_mem_region_t< DATA >::local (
    Ptr< T > p) const [inline]
```

Get the local address for driver address *p*.

#### Parameters

<i>p</i>	Driver address to translate.
----------	------------------------------

**Precondition**

*p* must be contained in this region.


**Returns**

Local address for the given driver address *p*.

Definition at line 629 of file [l4virtio](#).

Referenced by [L4virtio::Svr::Driver\\_mem\\_list\\_t< No\\_custom\\_data >::load\\_desc\(\)](#).

Here is the caller graph for this function:

**15.411.3.9 local\_base()**

```
template<typename DATA>
l4_addr_t L4virtio::Svr::Driver_mem_region_t< DATA >::local_base () const [inline]
```

**Returns**

The local base address.

Definition at line 587 of file [l4virtio](#).

**15.411.3.10 size()**

```
template<typename DATA>
l4_umword_t L4virtio::Svr::Driver_mem_region_t< DATA >::size () const [inline]
```

**Returns**

The size of the region in bytes.

Definition at line 590 of file [l4virtio](#).

The documentation for this class was generated from the following file:


- [l4/l4virtio/server/l4virtio](#)

## 15.412 L4virtio::Svr::Request\_processor Class Reference


Encapsulate the state for processing a VIRTIO request.

```
#include <virtio>
```

Inheritance diagram for L4virtio::Svr::Request\_processor:



Collaboration diagram for L4virtio::Svr::Request\_processor:



### Public Member Functions

- `template<typename DESC_MAN, typename ... ARGS>`  
`void start (DESC_MAN *dm, Virtqueue *ring, Virtqueue::Head\_desc const &request, ARGS... args)`  
*Start processing a new request.*
- `template<typename DESC_MAN, typename ... ARGS>`  
`Virtqueue::Request const & start (DESC_MAN *dm, Virtqueue::Request const &request, ARGS... args)`  
*Start processing a new request.*
- `Virtqueue::Desc::Flags current\_flags () const`  
*Get the flags of the currently processed descriptor.*

- bool `has_more` () const  
*Are there more chained descriptors?*
- template<typename DESC\_MAN, typename ... ARGS>  
bool `next` (DESC\_MAN \*dm, ARGS... args)  
*Switch to the next descriptor in a descriptor chain.*

### 15.412.1 Detailed Description

Encapsulate the state for processing a VIRTIO request.

A VIRTIO request is a possibly chained list of descriptors retrieved from the available ring of a virtqueue, using `Virtqueue::next_avail()`.

The descriptor processing depends on helper (DESC\_MAN) for interpreting the descriptors in the context of the device implementation.

DESC\_MAN has to provide the functionality to safely dereference a descriptor from a descriptor list.

The following methods must be provided by DESC\_MAN:

- DESC\_MAN::load\_desc(Virtqueue::Desc const &desc,  
Request\_processor const \*proc,  
Virtqueue::Desc const \*\*table)

This function is used to dereference `desc` as an indirect descriptor table, and must return a pointer to an indirect descriptor table.

- DESC\_MAN::load\_desc(Virtqueue::Desc const &desc,  
Request\_processor const \*proc, ...)

This function is used to dereference a descriptor as a normal data buffer, and '...' are the arguments that are passed to `start()` and `next()`.

Definition at line 472 of file `virtio`.

### 15.412.2 Member Function Documentation

#### 15.412.2.1 current\_flags()

```
Virtqueue::Desc::Flags L4virtio::Svr::Request_processor::current_flags () const [inline]
```

Get the flags of the currently processed descriptor.




**Returns**

The flags of the currently processed descriptor.

Definition at line 545 of file [virtio](#).

Referenced by [L4virtio::Svr::Virtio\\_gpio< Request\\_handler, Epiface >::Request\\_processor::get\\_request\(\)](#), and [L4virtio::Svr::Virtio\\_spi< Spi\\_request\\_handler, Epiface >::Request\\_processor::get\\_request\(\)](#).

Here is the caller graph for this function:

**15.412.2.2 has\_more()**

```
bool L4virtio::Svr::Request_processor::has_more () const [inline]
```

Are there more chained descriptors?


**Returns**

true if there are more chained descriptors in the current request.

Definition at line 553 of file [virtio](#).

Referenced by [L4virtio::Svr::Block\\_request< Ds\\_data >::data\\_size\(\)](#), and [L4virtio::Svr::Virtio\\_spi< Spi\\_request\\_handler, Epiface >::Request\\_processor::get\\_request\(\)](#).

Here is the caller graph for this function:



### 15.412.2.3 next()

```
template<typename DESC_MAN, typename ... ARGS>
bool L4virtio::Svr::Request_processor::next (
    DESC_MAN * dm,
    ARGS... args) [inline]
```

Switch to the next descriptor in a descriptor chain.

#### Template Parameters

<i>DESC_MAN</i>	Type of descriptor manager (implicit).
-----------------	--

#### Parameters

<i>dm</i>	Descriptor manager that is used to translate VIRTIO descriptor addresses.
<i>args</i>	Extra arguments passed to dm->load_desc()

#### Return values

<i>true</i>	A next descriptor is available.
<i>false</i>	No descriptor available.

#### Exceptions


<a href="#"><i>Bad_descriptor</i></a>	The <a href="#">next</a> index of this descriptor is invalid.
---------------------------------------	---

Definition at line 570 of file [virtio](#).


References [cxx::access\\_once\(\)](#), [L4virtio::Svr::Bad\\_descriptor::Bad\\_flags](#), [L4virtio::Svr::Bad\\_descriptor::Bad\\_next](#), and [L4\\_UNLIKELY](#).

Referenced by [L4virtio::Svr::Block\\_request<Ds\\_data>::data\\_size\(\)](#), [L4virtio::Svr::Virtio\\_gpio<Request\\_handler, Epiface>::Request\\_handler::get\\_request\(\)](#), [L4virtio::Svr::Virtio\\_i2c<Request\\_handler, Epiface>::Request\\_processor::get\\_request\(\)](#), [L4virtio::Svr::Virtio\\_spi<Spi\\_request\\_handler, Epiface>::Request\\_processor::get\\_request\(\)](#), [L4virtio::Svr::Console::Device::port\\_read\(\)](#), and [L4virtio::Svr::Console::Device::port\\_write\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



#### 15.412.2.4 start() [1/2]

```

template<typename DESC_MAN, typename ... ARGS>
void L4virtio::Svr::Request_processor::start (
    DESC_MAN * dm,
    Virtqueue * ring,
    Virtqueue::Head_desc const & request,
    ARGS... args) [inline]

```

Start processing a new request.

#### Template Parameters

<code>DESC_MAN</code>	Type of descriptor manager (implicit).
-----------------------	--

#### Parameters

---

<i>dm</i>	Descriptor manager that is used to translate VIRTIO descriptor addresses.
<i>ring</i>	VIRTIO ring of the request.
<i>request</i>	VIRTIO request from <a href="#">Virtqueue::next_avail()</a>
<i>args</i>	Extra arguments passed to <code>dm-&gt;load_desc()</code>

**Precondition**

The given request must be valid.

**Exceptions**


<a href="#">Bad_descriptor</a>	The descriptor has an invalid size or <code>load_desc()</code> has thrown an exception by itself.
--------------------------------	---

Definition at line 501 of file [virtio](#).


References [cxx::access\\_once\(\)](#), [L4virtio::Svr::Bad\\_descriptor::Bad\\_size](#), [L4virtio::Svr::Virtqueue::desc\(\)](#), [L4virtio::Svr::Virtqueue::Head\\_desc::desc\(\)](#), [L4\\_UNLIKELY](#), and [L4virtio::Virtqueue::num\(\)](#).

Referenced by [L4virtio::Svr::Block\\_request<Ds\\_data>::data\\_size\(\)](#), [Virtio\\_net\\_request::drop\\_requests\(\)](#), [L4virtio::Svr::Console::Virtio\\_con::handle\\_control\\_message\(\)](#), [L4virtio::Svr::Console::Device::port\\_read\(\)](#), [L4virtio::Svr::Console::Device::port\\_write\(\)](#), [L4virtio::Svr::Console::Virtio\\_con::send\\_control\\_message\(\)](#), and [start\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 15.412.2.5 start() [2/2]

```

template<typename DESC_MAN, typename ... ARGS>
Virtqueue::Request const & L4virtio::Svr::Request_processor::start (
    DESC_MAN * dm,
    Virtqueue::Request const & request,
    ARGS... args) [inline]

```

Start processing a new request.

#### Template Parameters

<code>DESC_MAN</code>	Type of descriptor manager (implicit).
-----------------------	--

#### Parameters

<code>dm</code>	Descriptor manager that is used to translate VIRTIO descriptor addresses.
<code>request</code>	VIRTIO request from <a href="#">Virtqueue::next_avail()</a>
<code>args</code>	Extra arguments passed to <code>dm-&gt;load_desc()</code>


**Precondition**

The given request must be valid.

Definition at line 534 of file [virtio](#).

References [start\(\)](#).

Here is the call graph for this function:



The documentation for this class was generated from the following file:


- `l4/l4virtio/server/virtio`

## 15.413 L4virtio::Svr::Scmi::Base\_attr\_t Struct Reference

SCMI base protocol attributes.

```
#include <virtio-scmi-device>
```

Collaboration diagram for L4virtio::Svr::Scmi::Base\_attr\_t:



- typedef [cxx::Bitfield](#)< decltype(attr\_raw), 8, 15 > **nagents\_bfm\_t**  
Type to access the *nagents* bits (8 to 15) of *attr\_raw*.
- constexpr [nagents\\_bfm\\_t::Val](#) **nagents** () const  
Get the *nagents* bits (8 to 15) of *attr\_raw*.
- constexpr [nagents\\_bfm\\_t::Ref](#) **nagents** ()  
Get a reference to the *nagents* bits (8 to 15) of *attr\_raw*.
  
- typedef [cxx::Bitfield](#)< decltype(attr\_raw), 0, 7 > **nprots\_bfm\_t**  
Type to access the *nprots* bits (0 to 7) of *attr\_raw*.
- constexpr [nprots\\_bfm\\_t::Val](#) **nprots** () const  
Get the *nprots* bits (0 to 7) of *attr\_raw*.
- constexpr [nprots\\_bfm\\_t::Ref](#) **nprots** ()  
Get a reference to the *nprots* bits (0 to 7) of *attr\_raw*.

### 15.413.1 Detailed Description

SCMI base protocol attributes.

Definition at line 90 of file [virtio-scmi-device](#).

The documentation for this struct was generated from the following file:


- I4/I4virtio/server/virtio-scmi-device

## 15.414 L4virtio::Svr::Scmi::Base\_proto Class Reference

Base class for the SCMI base protocol.


```
#include <virtio-scmi-device>
```

Inheritance diagram for L4virtio::Svr::Scmi::Base\_proto:





Collaboration diagram for L4virtio::Svr::Scmi::Base\_proto:



### 15.414.1 Detailed Description

Base class for the SCMI base protocol.

Use this class as a base to implement the base protocol.

Definition at line 458 of file [virtio-scmi-device](#).

The documentation for this class was generated from the following file:


- `l4/l4virtio/server/virtio-scmi-device`

## 15.415 L4virtio::Svr::Scmi::Perf\_proto Class Reference


Base class for the SCMI performance protocol.

```
#include <virtio-scmi-device>
```

Inheritance diagram for L4virtio::Svr::Scmi::Perf\_proto:



Collaboration diagram for L4virtio::Svr::Scmi::Perf\_proto:



### 15.415.1 Detailed Description

Base class for the SCMI performance protocol.

Use this class as a base to implement the performance protocol.

If you want to use this from a Uvmm Linux guest, the device tree needs to look something like this:

```

firmware {
    scmi {
        compatible = "arm,scmi-virtio";

        #address-cells = <1>;
        #size-cells = <0>;

        cpufreq: protocol@13 {
            reg = <0x13>;
            #clock-cells = <1>;
        };
    };
};
....

cpu@0 {
    device_type = "cpu";
    reg = <0x0>;
    clocks = <&cpufreq 0>; // domain_id
};
  
```

Definition at line 662 of file [virtio-scmi-device](#).

The documentation for this class was generated from the following file:


- l4/l4virtio/server/virtio-scmi-device

## 15.416 L4virtio::Svr::Scmi::Performance\_attr\_t Struct Reference

SCMI performance protocol attributes.

```
#include <virtio-scmi-device>
```

Collaboration diagram for L4virtio::Svr::Scmi::Performance\_attr\_t:



- typedef [cxx::Bitfield](#)< decltype(attr\_raw), 16, 16 > **power\_bfm\_t**  
Type to access the [power](#) bits (16 to 16) of *attr\_raw*.
- constexpr [power\\_bfm\\_t::Val](#) **power** () const  
Get the [power](#) bits (16 to 16) of *attr\_raw*.
- constexpr [power\\_bfm\\_t::Ref](#) **power** ()  
Get a reference to the [power](#) bits (16 to 16) of *attr\_raw*.
- typedef [cxx::Bitfield](#)< decltype(attr\_raw), 0, 15 > **domains\_bfm\_t**  
Type to access the [domains](#) bits (0 to 15) of *attr\_raw*.
- constexpr [domains\\_bfm\\_t::Val](#) **domains** () const  
Get the [domains](#) bits (0 to 15) of *attr\_raw*.
- constexpr [domains\\_bfm\\_t::Ref](#) **domains** ()  
Get a reference to the [domains](#) bits (0 to 15) of *attr\_raw*.

### 15.416.1 Detailed Description

SCMI performance protocol attributes.

Definition at line 112 of file [virtio-scmi-device](#).

The documentation for this struct was generated from the following file:

- l4/l4virtio/server/virtio-scmi-device

## 15.417 L4virtio::Svr::Scmi::Performance\_describe\_level\_t Struct Reference

SCMI performance describe level.

```
#include <virtio-scmi-device>
```

Collaboration diagram for L4virtio::Svr::Scmi::Performance\_describe\_level\_t:



### 15.417.1 Detailed Description

SCMI performance describe level.

Definition at line 150 of file [virtio-scmi-device](#).

The documentation for this struct was generated from the following file:


- l4/l4virtio/server/virtio-scmi-device

## 15.418 L4virtio::Svr::Scmi::Performance\_describe\_levels\_n\_t Struct Reference

SCMI performance describe levels numbers.

```
#include <virtio-scmi-device>
```

Collaboration diagram for L4virtio::Svr::Scmi::Performance\_describe\_levels\_n\_t:



- typedef [cxx::Bitfield](#)< decltype(num\_levels\_raw), 16, 31 > **nremain\_perf\_levels\_bfm\_t**  
Type to access the [nremain\\_perf\\_levels](#) bits (16 to 31) of [num\\_levels\\_raw](#).
- constexpr [nremain\\_perf\\_levels\\_bfm\\_t::Val](#) **nremain\_perf\_levels** () const  
Get the [nremain\\_perf\\_levels](#) bits (16 to 31) of [num\\_levels\\_raw](#).
- constexpr [nremain\\_perf\\_levels\\_bfm\\_t::Ref](#) **nremain\_perf\_levels** ()  
Get a reference to the [nremain\\_perf\\_levels](#) bits (16 to 31) of [num\\_levels\\_raw](#).
- typedef [cxx::Bitfield](#)< decltype(num\_levels\_raw), 0, 11 > **nperf\_levels\_bfm\_t**  
Type to access the [nperf\\_levels](#) bits (0 to 11) of [num\\_levels\\_raw](#).
- constexpr [nperf\\_levels\\_bfm\\_t::Val](#) **nperf\_levels** () const  
Get the [nperf\\_levels](#) bits (0 to 11) of [num\\_levels\\_raw](#).
- constexpr [nperf\\_levels\\_bfm\\_t::Ref](#) **nperf\_levels** ()  
Get a reference to the [nperf\\_levels](#) bits (0 to 11) of [num\\_levels\\_raw](#).

### 15.418.1 Detailed Description

SCMI performance describe levels numbers.

Definition at line 142 of file [virtio-scmi-device](#).

The documentation for this struct was generated from the following file:

- l4/l4virtio/server/virtio-scmi-device

## 15.419 L4virtio::Svr::Scmi::Performance\_domain\_attr\_t Struct Reference

SCMI performance domain protocol attributes.

```
#include <virtio-scmi-device>
```

Collaboration diagram for L4virtio::Svr::Scmi::Performance\_domain\_attr\_t:

L4virtio::Svr::Scmi ::Performance_domain _attr_t
<ul style="list-style-type: none"> <li>* set_limits_bfm_t</li> <li>* set_limits()</li> <li>* set_limits()</li> <li>* set_perf_level_bfm_t</li> <li>* set_perf_level()</li> <li>* set_perf_level()</li> <li>* perf_limits_change_notify_bfm_t</li> <li>* perf_limits_change_notify()</li> <li>* perf_limits_change_notify()</li> <li>* perf_level_change_notify_bfm_t</li> <li>* perf_level_change_notify()</li> <li>* perf_level_change_notify()</li> <li>* fast_channel_bfm_t</li> <li>* fast_channel()</li> <li>* fast_channel()</li> <li>* rate_limit_bfm_t</li> <li>* rate_limit()</li> <li>* rate_limit()</li> </ul>

- typedef [cxx::Bitfield](#)< decltype(attr\_raw), 31, 31 > **set\_limits\_bfm\_t**  
Type to access the [set\\_limits](#) bits (31 to 31) of *attr\_raw*.
- constexpr [set\\_limits\\_bfm\\_t::Val](#) **set\_limits** () const

- Get the *set\_limits* bits (31 to 31) of *attr\_raw*.

  - `constexpr set\_limits\_bfm\_t::Ref set_limits ()`  
 Get a reference to the *set\_limits* bits (31 to 31) of *attr\_raw*.
- `typedef cxx::Bitfield< decltype(attr_raw), 30, 30 > set_perf_level_bfm_t`  
 Type to access the *set\_perf\_level* bits (30 to 30) of *attr\_raw*.

  - `constexpr set\_perf\_level\_bfm\_t::Val set_perf_level () const`  
 Get the *set\_perf\_level* bits (30 to 30) of *attr\_raw*.
  - `constexpr set\_perf\_level\_bfm\_t::Ref set_perf_level ()`  
 Get a reference to the *set\_perf\_level* bits (30 to 30) of *attr\_raw*.
- `typedef cxx::Bitfield< decltype(attr_raw), 29, 29 > perf_limits_change_notify_bfm_t`  
 Type to access the *perf\_limits\_change\_notify* bits (29 to 29) of *attr\_raw*.

  - `constexpr perf\_limits\_change\_notify\_bfm\_t::Val perf_limits_change_notify () const`  
 Get the *perf\_limits\_change\_notify* bits (29 to 29) of *attr\_raw*.
  - `constexpr perf\_limits\_change\_notify\_bfm\_t::Ref perf_limits_change_notify ()`  
 Get a reference to the *perf\_limits\_change\_notify* bits (29 to 29) of *attr\_raw*.
- `typedef cxx::Bitfield< decltype(attr_raw), 28, 28 > perf_level_change_notify_bfm_t`  
 Type to access the *perf\_level\_change\_notify* bits (28 to 28) of *attr\_raw*.

  - `constexpr perf\_level\_change\_notify\_bfm\_t::Val perf_level_change_notify () const`  
 Get the *perf\_level\_change\_notify* bits (28 to 28) of *attr\_raw*.
  - `constexpr perf\_level\_change\_notify\_bfm\_t::Ref perf_level_change_notify ()`  
 Get a reference to the *perf\_level\_change\_notify* bits (28 to 28) of *attr\_raw*.
- `typedef cxx::Bitfield< decltype(attr_raw), 27, 27 > fast_channel_bfm_t`  
 Type to access the *fast\_channel* bits (27 to 27) of *attr\_raw*.

  - `constexpr fast\_channel\_bfm\_t::Val fast_channel () const`  
 Get the *fast\_channel* bits (27 to 27) of *attr\_raw*.
  - `constexpr fast\_channel\_bfm\_t::Ref fast_channel ()`  
 Get a reference to the *fast\_channel* bits (27 to 27) of *attr\_raw*.
- `typedef cxx::Bitfield< decltype(rate_limit_raw), 0, 19 > rate_limit_bfm_t`  
 Type to access the *rate\_limit* bits (0 to 19) of *rate\_limit\_raw*.

  - `constexpr rate\_limit\_bfm\_t::Val rate_limit () const`  
 Get the *rate\_limit* bits (0 to 19) of *rate\_limit\_raw*.
  - `constexpr rate\_limit\_bfm\_t::Ref rate_limit ()`  
 Get a reference to the *rate\_limit* bits (0 to 19) of *rate\_limit\_raw*.

### 15.419.1 Detailed Description

SCMI performance domain protocol attributes.

Definition at line 124 of file [virtio-scmi-device](#).

The documentation for this struct was generated from the following file:

- `I4/I4virtio/server/virtio-scmi-device`




## 15.420 L4virtio::Svr::Scmi::Proto< OBSERV > Struct Template Reference


Base class for all protocols.

```
#include <virtio-scmi-device>
```

Inheritance diagram for L4virtio::Svr::Scmi::Proto< OBSERV >:



Collaboration diagram for L4virtio::Svr::Scmi::Proto< OBSERV >:



### 15.420.1 Detailed Description

```
template<typename OBSERV>
struct L4virtio::Svr::Scmi::Proto< OBSERV >
```

Base class for all protocols.

Defines an interface for processing the virtio buffers for the implemented protocol.

Definition at line 299 of file [virtio-scmi-device](#).

The documentation for this struct was generated from the following file:


- [l4/l4virtio/server/virtio-scmi-device](#)

## 15.421 L4virtio::Svr::Scmi::Scmi\_dev Class Reference


A server implementation of the virtio-scmi protocol.

```
#include <virtio-scmi-device>
```

Inheritance diagram for L4virtio::Svr::Scmi::Scmi\_dev:



Collaboration diagram for L4virtio::Svr::Scmi::Scmi\_dev:



### Public Member Functions

- void **add\_proto** ([l4\\_uint32\\_t](#) id, [Proto](#)< Scmi\_dev > \*proto)

*Add an actual protocol implementation with the given id to the server.*

### Public Member Functions inherited from [L4virtio::Svr::Device\\_t< No\\_custom\\_data >](#)

- virtual bool **check\_features** ()

- callback for checking the subset of accepted features*
- virtual void **cfg\_changed** (unsigned)
  - callback for client device configuration changes*
- virtual void **register\_driver\_irq** (unsigned idx)
  - Callback for registering an notification IRQ (multi IRQ).*
- virtual **L4::Cap**< **L4::Irq** > **device\_notify\_irq** (unsigned idx)
  - Callback to gather the device notification IRQ (multi IRQ).*
- virtual unsigned **num\_events\_supported** () const
  - Return the highest notification index supported.*
- **Device\_t** (**Dev\_config** \*dev\_config)
  - Make a device for the given config.*
- **Mem\_list** const \* **mem\_info** () const
  - Get the memory region list used for this device.*
- void **reset\_queue\_config** (unsigned idx, unsigned num\_max, bool inc\_generation=false, unsigned device\_notify\_index=0)
  - Trigger reset for the configuration space for queue idx.*
- void **init\_mem\_info** (unsigned num)
  - Initialize the memory region list to the given maximum.*
- void **device\_error** ()
  - Transition device into DEVICE\_NEEDS\_RESET state.*
- bool **setup\_queue** (Virtqueue \*q, unsigned qn, unsigned num\_max)
  - Enable/disable the specified queue.*
- bool **handle\_mem\_cmd\_write** ()
  - Check for a value in the cmd register and handle a write.*
- void **enable\_trusted\_ds\_validation** ()
  - Enable trusted dataspace validation.*
- void **add\_trusted\_dataspaces** (std::shared\_ptr< Ds\_vector const > ds)
  - Provide a list of trusted dataspaces that can be used for validation.*

### Additional Inherited Members

### Protected Attributes inherited from **L4virtio::Svr::Device\_t**< **No\_custom\_data** >

- **Mem\_list** **\_mem\_info**
  - Memory region list.*

## 15.421.1 Detailed Description

A server implementation of the virtio-scmi protocol.

Use this class as a base to implement your own specific SCMI device.

SCMI defines multiple protocols which can be optionally handled. This server implementation is flexible enough to handle any combination of them. The user of this server has to deviate from the provided **Proto** classes (for the protocols he want to handle) and needs to implement the required callbacks.

Right now, support for the base and the performance protocol is provided.

The base protocol is mandatory.

If you want to use this from a Uvmm Linux guest, the device tree needs to look something like this:

```
firmware {
    scmi {
        compatible = "arm,scmi-virtio";

        #address-cells = <1>;
        #size-cells = <0>;

        // ... supported protocols ...
    };
};
```

Definition at line 336 of file [virtio-scmi-device](#).

The documentation for this class was generated from the following file:

- l4/l4virtio/server/virtio-scmi-device

## 15.422 L4virtio::Svr::Scmi::Scmi\_hdr\_t Struct Reference

SCMI header.

```
#include <virtio-scmi-device>
```

Collaboration diagram for L4virtio::Svr::Scmi::Scmi\_hdr\_t:



- typedef [cxx::Bitfield](#)< decltype(hdr\_raw), 18, 27 > **token\_bfm\_t**  
Type to access the *token* bits (18 to 27) of *hdr\_raw*.

- constexpr [token\\_bfm\\_t::Val](#) **token** () const  
Get the *token* bits (18 to 27) of *hdr\_raw*.
- constexpr [token\\_bfm\\_t::Ref](#) **token** ()  
Get a reference to the *token* bits (18 to 27) of *hdr\_raw*.
  
- typedef [cxx::Bitfield](#)< decltype(hdr\_raw), 10, 17 > **protocol\_id\_bfm\_t**  
Type to access the *protocol\_id* bits (10 to 17) of *hdr\_raw*.
- constexpr [protocol\\_id\\_bfm\\_t::Val](#) **protocol\_id** () const  
Get the *protocol\_id* bits (10 to 17) of *hdr\_raw*.
- constexpr [protocol\\_id\\_bfm\\_t::Ref](#) **protocol\_id** ()  
Get a reference to the *protocol\_id* bits (10 to 17) of *hdr\_raw*.
  
- typedef [cxx::Bitfield](#)< decltype(hdr\_raw), 8, 9 > **message\_type\_bfm\_t**  
Type to access the *message\_type* bits (8 to 9) of *hdr\_raw*.
- constexpr [message\\_type\\_bfm\\_t::Val](#) **message\_type** () const  
Get the *message\_type* bits (8 to 9) of *hdr\_raw*.
- constexpr [message\\_type\\_bfm\\_t::Ref](#) **message\_type** ()  
Get a reference to the *message\_type* bits (8 to 9) of *hdr\_raw*.
  
- typedef [cxx::Bitfield](#)< decltype(hdr\_raw), 0, 7 > **message\_id\_bfm\_t**  
Type to access the *message\_id* bits (0 to 7) of *hdr\_raw*.
- constexpr [message\\_id\\_bfm\\_t::Val](#) **message\_id** () const  
Get the *message\_id* bits (0 to 7) of *hdr\_raw*.
- constexpr [message\\_id\\_bfm\\_t::Ref](#) **message\_id** ()  
Get a reference to the *message\_id* bits (0 to 7) of *hdr\_raw*.

### 15.422.1 Detailed Description

SCMI header.

Definition at line 45 of file [virtio-scmi-device](#).


The documentation for this struct was generated from the following file:

- I4/I4virtio/server/virtio-scmi-device





Collaboration diagram for L4virtio::Svr::Virtio\_gpio< Request\_handler, Epiface >:



## Data Structures

- struct `Irq_handler`  
Handler for an gpio pin irq.
- struct `Host_irq`  
Handler for the host irq.
- struct `Request_processor`  
Generic handler for the Virtio requests.

## Public Member Functions

- void **reset** () override  
*reset callback, called for doing a device reset*
- bool **check\_queues** () override  
*callback for checking if the queues at DRIVER\_OK transition*
- int **reconfig\_queue** (unsigned idx) override  
*callback for client queue-config request*
- void **trigger\_driver\_config\_irq** () override  
*callback for triggering configuration change notification IRQ*
- [L4::Cap](#) < [L4::Irq](#) > **device\_notify\_irq** () const override  
*callback to gather the device notification IRQ (old-style)*
- void **register\_single\_driver\_irq** () override  
*callback for registering a single guest IRQ for all queues (old-style)*

## Public Member Functions inherited from [L4virtio::Svr::Device\\_t](#) < [No\\_custom\\_data](#) >

- virtual bool **check\_features** ()  
*callback for checking the subset of accepted features*
- virtual void **cfg\_changed** (unsigned)  
*callback for client device configuration changes*
- virtual void **register\_driver\_irq** (unsigned idx)  
*Callback for registering an notification IRQ (multi IRQ).*
- virtual [L4::Cap](#) < [L4::Irq](#) > **device\_notify\_irq** (unsigned idx)  
*Callback to gather the device notification IRQ (multi IRQ).*
- virtual unsigned **num\_events\_supported** () const  
*Return the highest notification index supported.*
- **Device\_t** ([Dev\\_config](#) \*dev\_config)  
*Make a device for the given config.*
- Mem\_list const \* **mem\_info** () const  
*Get the memory region list used for this device.*
- void **reset\_queue\_config** (unsigned idx, unsigned num\_max, bool inc\_generation=false, unsigned device\_notify\_index=0)  
*Trigger reset for the configuration space for queue idx.*
- void **init\_mem\_info** (unsigned num)  
*Initialize the memory region list to the given maximum.*
- void **device\_error** ()  
*Transition device into DEVICE\_NEEDS\_RESET state.*
- bool **setup\_queue** (Virtqueue \*q, unsigned qn, unsigned num\_max)  
*Enable/disable the specified queue.*
- bool **handle\_mem\_cmd\_write** ()  
*Check for a value in the cmd register and handle a write.*
- void **enable\_trusted\_ds\_validation** ()  
*Enable trusted dataspace validation.*
- void **add\_trusted\_dataspaces** (std::shared\_ptr < [Ds\\_vector](#) const > ds)  
*Provide a list of trusted dataspaces that can be used for validation.*

**Public Member Functions inherited from L4::Epiface\_t0< L4virtio::Device, L4::Epiface >**

- [Type\\_info::Demand](#) **get\_buffer\_demand** () const  
*Get the server-side buffer demand based in IFACE.*
- [Cap< L4virtio::Device >](#) **obj\_cap** () const  
*Get the (typed) capability to this object.*

**Public Member Functions inherited from L4::Epiface**

- **Epiface** ()  
*Make a server object.*
- virtual **~Epiface** ()=0  
*Destroy the object.*
- Stored\_cap [obj\\_cap](#) () const  
*Get the capability to the kernel object belonging to this object.*
- [Server\\_iface](#) \* **server\_iface** () const  
*Get pointer to server interface at which the object is currently registered.*
- int **set\_server** ([Server\\_iface](#) \*srv, [Cap< void >](#) cap, bool managed=false)  
*Set server registration info for the object.*
- void **set\_obj\_cap** ([Cap< void >](#) const &cap)  
*Deprecated server registration function.*

**Additional Inherited Members****Public Types inherited from L4::Epiface\_t0< L4virtio::Device, L4::Epiface >**

- typedef [L4virtio::Device](#) **Interface**  
*Data type of the IPC interface definition.*

**Public Types inherited from L4::Epiface**

- typedef [lpc\\_svr::Server\\_iface](#) **Server\_iface**  
*Type for abstract server interface.*
- typedef [lpc\\_svr::Server\\_iface::Demand](#) **Demand**  
*Type for server-side receive buffer demand.*

**Protected Attributes inherited from L4virtio::Svr::Device\_t< No\_custom\_data >**

- **Mem\_list\_mem\_info**  
*Memory region list.*

### 15.423.1 Detailed Description

```
template<typename Request_handler, typename Epiface = L4virtio::Device>
class L4virtio::Svr::Virtio_gpio< Request_handler, Epiface >
```

A server implementation of the virtio-gpio protocol.

#### Template Parameters

<i>Request_handler</i>	<p>The type that is used to handle incoming requests. Needs to have:</p> <ul style="list-style-type: none"> <li>• <code>bool get_direction(l4_uint16_t gpio, l4_uint8_t *dir)</code></li> <li>• <code>bool set_direction(l4_uint16_t gpio, l4_uint8_t dir)</code></li> <li>• <code>bool get_value(l4_uint16_t gpio, l4_uint8_t *val)</code></li> <li>• <code>bool set_value(l4_uint16_t gpio, l4_uint8_t val)</code></li> <li>• <code>bool set_irq_type(l4_uint16_t gpio, l4_uint8_t mode)</code></li> <li>• <code>bool enable_irq(l4_uint16_t gpio, std::shared_ptr&lt;Virtio_gpio::Irq_handler&gt; const &amp;hdl) functions.</code></li> </ul>
<i>Epiface</i>	The Epiface to derive from. Defaults to <a href="#">L4virtio::Device</a> .

Definition at line 142 of file [virtio-gpio-device](#).

The documentation for this class was generated from the following file:


- l4/l4virtio/server/virtio-gpio-device

### 15.424 L4virtio::Svr::Virtio\_gpio< Request\_handler, Epiface >::Host\_irq Struct Reference


Handler for the host irq.

```
#include <virtio-gpio-device>
```

Inheritance diagram for L4virtio::Svr::Virtio\_gpio< Request\_handler, Epiface >::Host\_irq:



Collaboration diagram for L4virtio::Svr::Virtio\_gpio< Request\_handler, Epiface >::Host\_irq:



### Additional Inherited Members

### Public Types inherited from L4::Epiface\_t0< void, Epiface >

- typedef void **Interface**

*Data type of the IPC interface definition.*

## Public Types inherited from L4::Epiface

- typedef [lpc\\_svr::Server\\_iface](#) **Server\_iface**  
*Type for abstract server interface.*
- typedef [lpc\\_svr::Server\\_iface::Demand](#) **Demand**  
*Type for server-side receive buffer demand.*

## Public Member Functions inherited from L4::lrqep\_t< Host\_irq >

- [Cap< L4::lrq >](#) **obj\_cap** () const  
*Get the (typed) capability to this object.*

## Public Member Functions inherited from L4::Epiface\_t0< void, Epiface >

- [Type\\_info::Demand](#) **get\_buffer\_demand** () const  
*Get the server-side buffer demand based in IFACE.*
- [Cap< void >](#) **obj\_cap** () const  
*Get the (typed) capability to this object.*

## Public Member Functions inherited from L4::Epiface

- **Epiface** ()  
*Make a server object.*
- virtual **~Epiface** ()=0  
*Destroy the object.*
- Stored\_cap **obj\_cap** () const  
*Get the capability to the kernel object belonging to this object.*
- [Server\\_iface](#) \* **server\_iface** () const  
*Get pointer to server interface at which the object is currently registered.*
- int **set\_server** ([Server\\_iface](#) \*srv, [Cap< void >](#) cap, bool managed=false)  
*Set server registration info for the object.*
- void **set\_obj\_cap** ([Cap< void >](#) const &cap)  
*Deprecated server registration function.*

### 15.424.1 Detailed Description

```
template<typename Request_handler, typename Epiface = L4virtio::Device>
struct L4virtio::Svr::Virtio_gpio< Request_handler, Epiface >::Host_irq
```

Handler for the host irq.

An [L4::lrqep\\_t](#) to handle irq's send to the server.

Definition at line 198 of file [virtio-gpio-device](#).

The documentation for this struct was generated from the following file:

- l4/l4virtio/server/virtio-gpio-device

## 15.425 L4virtio::Svr::Virtio\_gpio< Request\_handler, Epiface >::Irq\_handler Struct Reference

Handler for an gpio pin irq.

```
#include <virtio-gpio-device>
```

Collaboration diagram for L4virtio::Svr::Virtio\_gpio< Request\_handler, Epiface >::Irq\_handler:



### 15.425.1 Detailed Description

```
template<typename Request_handler, typename Epiface = L4virtio::Device>
struct L4virtio::Svr::Virtio_gpio< Request_handler, Epiface >::Irq_handler
```

Handler for an gpio pin irq.

This notifies the virtio client that an gpio pin irq happened or the operation was canceled.

This needs to be called by any server implementation of the [Virtio\\_gpio](#) class, after an irq was enabled with the enable method of the [Gpio\\_request\\_handler](#).

Definition at line [166](#) of file [virtio-gpio-device](#).

The documentation for this struct was generated from the following file:

- [I4/I4virtio/server/virtio-gpio-device](#)




## 15.426 L4virtio::Svr::Virtio\_gpio< Request\_handler, Epiface >::Request\_processor Struct Reference


Generic handler for the Virtio requests.

```
#include <virtio-gpio-device>
```

Inheritance diagram for L4virtio::Svr::Virtio\_gpio< Request\_handler, Epiface >::Request\_processor:



Collaboration diagram for L4virtio::Svr::Virtio\_gpio< Request\_handler, Epiface >::Request\_processor:



## Protected Member Functions

- `template<typename T>`  
`T get_request ()`

The driver prepares the GPIO request in two data parts: 1st: in\_hdr 2nd: out\_hdr.

## Additional Inherited Members

### Public Member Functions inherited from L4virtio::Svr::Request\_processor

- template<typename DESC\_MAN, typename ... ARGS>  
void [start](#) (DESC\_MAN \*dm, Virtqueue \*ring, [Virtqueue::Head\\_desc](#) const &request, ARGS... args)  
*Start processing a new request.*
- template<typename DESC\_MAN, typename ... ARGS>  
Virtqueue::Request const & [start](#) (DESC\_MAN \*dm, Virtqueue::Request const &request, ARGS... args)  
*Start processing a new request.*
- [Virtqueue::Desc::Flags](#) [current\\_flags](#) () const  
*Get the flags of the currently processed descriptor.*
- bool [has\\_more](#) () const  
*Are there more chained descriptors?*
- template<typename DESC\_MAN, typename ... ARGS>  
bool [next](#) (DESC\_MAN \*dm, ARGS... args)  
*Switch to the next descriptor in a descriptor chain.*

## 15.426.1 Detailed Description

template<typename Request\_handler, typename Epiface = L4virtio::Device>  
struct L4virtio::Svr::Virtio\_gpio< Request\_handler, Epiface >::Request\_processor

Generic handler for the Virtio requests.

Definition at line 213 of file [virtio-gpio-device](#).

## 15.426.2 Member Function Documentation

### 15.426.2.1 get\_request()

```
template<typename Request_handler, typename Epiface = L4virtio::Device>
template<typename T>
T L4virtio::Svr::Virtio_gpio< Request_handler, Epiface >::Request_processor::get_request ()
[inline], [protected]
```


The driver prepares the GPIO request in two data parts: 1st: in\_hdr 2rd: out\_hdr.

This parses the two Data\_buffers and create the Gpio\_\* structure.

Definition at line 241 of file [virtio-gpio-device](#).

References [L4virtio::Svr::Request\\_processor::current\\_flags\(\)](#), and [L4virtio::Svr::Request\\_processor::next\(\)](#).

Here is the call graph for this function:



The documentation for this struct was generated from the following file:


- `I4/I4virtio/server/virtio-gpio-device`

## 15.427 L4virtio::Svr::Virtio\_i2c< Request\_handler, Epiface > Class Template Reference


A server implementation of the virtio-i2c protocol.

```
#include <virtio-i2c-device>
```

Inheritance diagram for L4virtio::Svr::Virtio\_i2c< Request\_handler, Epiface >:



Collaboration diagram for L4virtio::Svr::Virtio\_i2c< Request\_handler, Epiface >:



## Data Structures

- class `Host_irq`  
*Handler for the host irq.*
- class `Request_processor`  
*Handler for the Virtio requests.*

## Public Member Functions

- void **reset** () override  
*reset callback, called for doing a device reset*
- bool **check\_queues** () override  
*callback for checking if the queues at DRIVER\_OK transition*
- int **reconfig\_queue** (unsigned idx) override  
*callback for client queue-config request*
- void **trigger\_driver\_config\_irq** () override  
*callback for triggering configuration change notification IRQ*
- [L4::Cap](#) < [L4::Irq](#) > **device\_notify\_irq** () const override  
*callback to gather the device notification IRQ (old-style)*
- void **register\_single\_driver\_irq** () override  
*callback for registering a single guest IRQ for all queues (old-style)*

## Public Member Functions inherited from [L4virtio::Svr::Device\\_t](#) < [No\\_custom\\_data](#) >

- virtual bool **check\_features** ()  
*callback for checking the subset of accepted features*
- virtual void **cfg\_changed** (unsigned)  
*callback for client device configuration changes*
- virtual void **register\_driver\_irq** (unsigned idx)  
*Callback for registering an notification IRQ (multi IRQ).*
- virtual [L4::Cap](#) < [L4::Irq](#) > **device\_notify\_irq** (unsigned idx)  
*Callback to gather the device notification IRQ (multi IRQ).*
- virtual unsigned **num\_events\_supported** () const  
*Return the highest notification index supported.*
- [Device\\_t](#) ([Dev\\_config](#) \*dev\_config)  
*Make a device for the given config.*
- [Mem\\_list](#) const \* **mem\_info** () const  
*Get the memory region list used for this device.*
- void **reset\_queue\_config** (unsigned idx, unsigned num\_max, bool inc\_generation=false, unsigned device\_notify\_index=0)  
*Trigger reset for the configuration space for queue idx.*
- void **init\_mem\_info** (unsigned num)  
*Initialize the memory region list to the given maximum.*
- void **device\_error** ()  
*Transition device into DEVICE\_NEEDS\_RESET state.*
- bool **setup\_queue** ([Virtqueue](#) \*q, unsigned qn, unsigned num\_max)  
*Enable/disable the specified queue.*
- bool **handle\_mem\_cmd\_write** ()  
*Check for a value in the cmd register and handle a write.*
- void **enable\_trusted\_ds\_validation** ()  
*Enable trusted dataspace validation.*
- void **add\_trusted\_dataspaces** ([std::shared\\_ptr](#) < [Ds\\_vector](#) const > ds)  
*Provide a list of trusted dataspaces that can be used for validation.*

**Public Member Functions inherited from L4::Epiface\_t0< L4virtio::Device, L4::Epiface >**

- [Type\\_info::Demand](#) **get\_buffer\_demand** () const  
*Get the server-side buffer demand based in IFACE.*
- [Cap< L4virtio::Device >](#) **obj\_cap** () const  
*Get the (typed) capability to this object.*

**Public Member Functions inherited from L4::Epiface**

- **Epiface** ()  
*Make a server object.*
- virtual **~Epiface** ()=0  
*Destroy the object.*
- Stored\_cap [obj\\_cap](#) () const  
*Get the capability to the kernel object belonging to this object.*
- [Server\\_iface](#) \* **server\_iface** () const  
*Get pointer to server interface at which the object is currently registered.*
- int **set\_server** ([Server\\_iface](#) \*srv, [Cap< void >](#) cap, bool managed=false)  
*Set server registration info for the object.*
- void **set\_obj\_cap** ([Cap< void >](#) const &cap)  
*Deprecated server registration function.*

**Additional Inherited Members****Public Types inherited from L4::Epiface\_t0< L4virtio::Device, L4::Epiface >**

- typedef [L4virtio::Device](#) **Interface**  
*Data type of the IPC interface definition.*

**Public Types inherited from L4::Epiface**

- typedef [lpc\\_svr::Server\\_iface](#) **Server\_iface**  
*Type for abstract server interface.*
- typedef [lpc\\_svr::Server\\_iface::Demand](#) **Demand**  
*Type for server-side receive buffer demand.*

**Protected Attributes inherited from L4virtio::Svr::Device\_t< No\_custom\_data >**

- **Mem\_list\_mem\_info**  
*Memory region list.*

### 15.427.1 Detailed Description

```
template<typename Request_handler, typename Epiface = L4virtio::Device>
class L4virtio::Svr::Virtio_i2c< Request_handler, Epiface >
```

A server implementation of the virtio-i2c protocol.

#### Template Parameters

<i>Request_handler</i>	The type that is used to handle incoming requests. Needs to have <code>handle_read(l4_uint8_t *, unsigned)</code> and <code>handle_write(l4_uint8_t const *, unsigned)</code> functions.
<i>Epiface</i>	The Epiface to derive from. Defaults to <code>L4virtio::Device</code> .

Definition at line 86 of file [virtio-i2c-device](#).

The documentation for this class was generated from the following file:

- `l4/l4virtio/server/virtio-i2c-device`


## 15.428 L4virtio::Svr::Virtio\_i2c< Request\_handler, Epiface >::Host\_irq Class Reference

Handler for the host irq.


```
#include <virtio-i2c-device>
```



Inheritance diagram for L4virtio::Svr::Virtio\_i2c< Request\_handler, Epiface >::Host\_irq:



Collaboration diagram for L4virtio::Svr::Virtio\_i2c< Request\_handler, Epiface >::Host\_irq:



#### Additional Inherited Members

#### Public Types inherited from L4::Epiface\_t0< void, Epiface >

- typedef void **Interface**

*Data type of the IPC interface definition.*

## Public Types inherited from L4::Epiface

- typedef [lpc\\_svr::Server\\_iface](#) **Server\_iface**  
*Type for abstract server interface.*
- typedef [lpc\\_svr::Server\\_iface::Demand](#) **Demand**  
*Type for server-side receive buffer demand.*

## Public Member Functions inherited from L4::lrqep\_t< Host\_irq >

- [Cap< L4::lrq >](#) **obj\_cap** () const  
*Get the (typed) capability to this object.*

## Public Member Functions inherited from L4::Epiface\_t0< void, Epiface >

- [Type\\_info::Demand](#) **get\_buffer\_demand** () const  
*Get the server-side buffer demand based in IFACE.*
- [Cap< void >](#) **obj\_cap** () const  
*Get the (typed) capability to this object.*

## Public Member Functions inherited from L4::Epiface

- **Epiface** ()  
*Make a server object.*
- virtual **~Epiface** ()=0  
*Destroy the object.*
- Stored\_cap **obj\_cap** () const  
*Get the capability to the kernel object belonging to this object.*
- [Server\\_iface](#) \* **server\_iface** () const  
*Get pointer to server interface at which the object is currently registered.*
- int **set\_server** ([Server\\_iface](#) \*srv, [Cap< void >](#) cap, bool managed=false)  
*Set server registration info for the object.*
- void **set\_obj\_cap** ([Cap< void >](#) const &cap)  
*Deprecated server registration function.*

### 15.428.1 Detailed Description

```
template<typename Request_handler, typename Epiface = L4virtio::Device>
class L4virtio::Svr::Virtio_i2c< Request_handler, Epiface >::Host_irq
```

Handler for the host irq.

An [L4::lrqep\\_t](#) to handle irq's send to the server.

Definition at line 106 of file [virtio-i2c-device](#).

The documentation for this class was generated from the following file:


- I4/I4virtio/server/virtio-i2c-device

## 15.429 L4virtio::Svr::Virtio\_i2c< Request\_handler, Epiface >::Request\_processor Class Reference


Handler for the Virtio requests.

```
#include <virtio-i2c-device>
```

Inheritance diagram for L4virtio::Svr::Virtio\_i2c< Request\_handler, Epiface >::Request\_processor:



Collaboration diagram for L4virtio::Svr::Virtio\_i2c< Request\_handler, Epiface >::Request\_processor:



## Public Member Functions

- I2c\_req [get\\_request](#) ()

*Linux prepares the I2C request in three data parts: 1st: out\_hdr 2nd: buffer (optional) 3rd: in\_hdr.*

## Public Member Functions inherited from [L4virtio::Svr::Request\\_processor](#)

- template<typename DESC\_MAN, typename ... ARGS>  
void [start](#) (DESC\_MAN \*dm, Virtqueue \*ring, [Virtqueue::Head\\_desc](#) const &request, ARGS... args)  
*Start processing a new request.*
- template<typename DESC\_MAN, typename ... ARGS>  
Virtqueue::Request const & [start](#) (DESC\_MAN \*dm, Virtqueue::Request const &request, ARGS... args)  
*Start processing a new request.*
- [Virtqueue::Desc::Flags](#) [current\\_flags](#) () const  
*Get the flags of the currently processed descriptor.*
- bool [has\\_more](#) () const  
*Are there more chained descriptors?*
- template<typename DESC\_MAN, typename ... ARGS>  
bool [next](#) (DESC\_MAN \*dm, ARGS... args)  
*Switch to the next descriptor in a descriptor chain.*

### 15.429.1 Detailed Description

```
template<typename Request_handler, typename Epiface = L4virtio::Device>
class L4virtio::Svr::Virtio_i2c< Request_handler, Epiface >::Request_processor
```

Handler for the Virtio requests.

Definition at line 123 of file [virtio-i2c-device](#).

### 15.429.2 Member Function Documentation

#### 15.429.2.1 get\_request()

```
template<typename Request_handler, typename Epiface = L4virtio::Device>
I2c_req L4virtio::Svr::Virtio_i2c< Request_handler, Epiface >::Request_processor::get_request
() [inline]
```


Linux prepares the I2C request in three data parts: 1st: out\_hdr 2nd: buffer (optional) 3rd: in\_hdr.

This parses the three Data\_buffers and recreate the virtio\_i2c\_req structure.

Definition at line 172 of file [virtio-i2c-device](#).

References [L4virtio::Svr::Data\\_buffer::left](#), [L4virtio::Svr::Request\\_processor::next\(\)](#), and [L4virtio::Svr::Data\\_buffer::pos](#).

Here is the call graph for this function:



The documentation for this class was generated from the following file:


- [l4/l4virtio/server/virtio-i2c-device](#)

## 15.430 L4virtio::Svr::Virtio\_rng< Rnd\_state, Epiface > Class Template Reference


A server implementation of the virtio-rng protocol.

```
#include <virtio-rng-device>
```

Inheritance diagram for L4virtio::Svr::Virtio\_rng< Rnd\_state, Epiface >:



Collaboration diagram for L4virtio::Svr::Virtio\_rng< Rnd\_state, Epiface >:



## Data Structures

- class [Host\\_irq](#)  
Handler for the host irq.
- class [Request\\_processor](#)  
Handler for the Virtio requests.



## Public Member Functions

- void **reset** () override  
*reset callback, called for doing a device reset*
- bool **check\_queues** () override  
*callback for checking if the queues at DRIVER\_OK transition*
- int **reconfig\_queue** (unsigned idx) override  
*callback for client queue-config request*
- void **trigger\_driver\_config\_irq** () override  
*callback for triggering configuration change notification IRQ*
- L4::Cap< L4::Irq > **device\_notify\_irq** () const override  
*callback to gather the device notification IRQ (old-style)*
- void **register\_single\_driver\_irq** () override  
*callback for registering a single guest IRQ for all queues (old-style)*

## Public Member Functions inherited from L4virtio::Svr::Device\_t< No\_custom\_data >

- virtual bool **check\_features** ()  
*callback for checking the subset of accepted features*
- virtual void **cfg\_changed** (unsigned)  
*callback for client device configuration changes*
- virtual void **register\_driver\_irq** (unsigned idx)  
*Callback for registering an notification IRQ (multi IRQ).*
- virtual L4::Cap< L4::Irq > **device\_notify\_irq** (unsigned idx)  
*Callback to gather the device notification IRQ (multi IRQ).*
- virtual unsigned **num\_events\_supported** () const  
*Return the highest notification index supported.*
- **Device\_t** (Dev\_config \*dev\_config)  
*Make a device for the given config.*
- Mem\_list const \* **mem\_info** () const  
*Get the memory region list used for this device.*
- void **reset\_queue\_config** (unsigned idx, unsigned num\_max, bool inc\_generation=false, unsigned device\_notify\_index=0)  
*Trigger reset for the configuration space for queue idx.*
- void **init\_mem\_info** (unsigned num)  
*Initialize the memory region list to the given maximum.*
- void **device\_error** ()  
*Transition device into DEVICE\_NEEDS\_RESET state.*
- bool **setup\_queue** (Virtqueue \*q, unsigned qn, unsigned num\_max)  
*Enable/disable the specified queue.*
- bool **handle\_mem\_cmd\_write** ()  
*Check for a value in the cmd register and handle a write.*
- void **enable\_trusted\_ds\_validation** ()  
*Enable trusted dataspace validation.*
- void **add\_trusted\_dataspaces** (std::shared\_ptr< Ds\_vector const > ds)  
*Provide a list of trusted dataspaces that can be used for validation.*

## Public Member Functions inherited from [L4::Epiface\\_t0< L4virtio::Device, L4::Epiface >](#)

- [Type\\_info::Demand](#) **get\_buffer\_demand** () const  
*Get the server-side buffer demand based in IFACE.*
- [Cap< L4virtio::Device >](#) **obj\_cap** () const  
*Get the (typed) capability to this object.*

## Public Member Functions inherited from [L4::Epiface](#)

- **Epiface** ()  
*Make a server object.*
- virtual **~Epiface** ()=0  
*Destroy the object.*
- Stored\_cap [obj\\_cap](#) () const  
*Get the capability to the kernel object belonging to this object.*
- [Server\\_iface](#) \* **server\_iface** () const  
*Get pointer to server interface at which the object is currently registered.*
- int **set\_server** ([Server\\_iface](#) \*srv, [Cap< void >](#) cap, bool managed=false)  
*Set server registration info for the object.*
- void **set\_obj\_cap** ([Cap< void >](#) const &cap)  
*Deprecated server registration function.*

## Additional Inherited Members

## Public Types inherited from [L4::Epiface\\_t0< L4virtio::Device, L4::Epiface >](#)

- typedef [L4virtio::Device](#) **Interface**  
*Data type of the IPC interface definition.*

## Public Types inherited from [L4::Epiface](#)

- typedef [lpc\\_svr::Server\\_iface](#) **Server\_iface**  
*Type for abstract server interface.*
- typedef [lpc\\_svr::Server\\_iface::Demand](#) **Demand**  
*Type for server-side receive buffer demand.*

## Protected Attributes inherited from [L4virtio::Svr::Device\\_t< No\\_custom\\_data >](#)

- **Mem\_list\_mem\_info**  
*Memory region list.*

### 15.430.1 Detailed Description

```
template<typename Rnd_state, typename Epiface = L4virtio::Device>
class L4virtio::Svr::Virtio_rng< Rnd_state, Epiface >
```

A server implementation of the virtio-rng protocol.

#### Template Parameters

<i>Rnd_state</i>	The type that implements the random data generation. <code>Rnd_state::get_random(int len, unsigned char *buf)</code> is called to get len random bytes written into buf TODO: virtio-rng supports providing less random bytes then requested. This API currently does not support that, as I do not have a test case.
<i>Epiface</i>	The Epiface to derive from. Defaults to <code>L4virtio::Device</code> .

Definition at line 33 of file [virtio-rng-device](#).

The documentation for this class was generated from the following file:


- `l4/l4virtio/server/virtio-rng-device`

## 15.431 L4virtio::Svr::Virtio\_rng< Rnd\_state, Epiface >::Host\_irq Class Reference


Handler for the host irq.

```
#include <virtio-rng-device>
```

Inheritance diagram for L4virtio::Svr::Virtio\_rng< Rnd\_state, Epiface >::Host\_irq:



Collaboration diagram for L4virtio::Svr::Virtio\_rng< Rnd\_state, Epiface >::Host\_irq:



### Additional Inherited Members

### Public Types inherited from L4::Epiface\_t0< void, Epiface >

- typedef void **Interface**

*Data type of the IPC interface definition.*

## Public Types inherited from [L4::Epiface](#)

- typedef [lpc\\_svr::Server\\_iface](#) **Server\_iface**  
*Type for abstract server interface.*
- typedef [lpc\\_svr::Server\\_iface::Demand](#) **Demand**  
*Type for server-side receive buffer demand.*

## Public Member Functions inherited from [L4::lrqep\\_t< Host\\_irq >](#)

- [Cap< L4::lrq > obj\\_cap](#) () const  
*Get the (typed) capability to this object.*

## Public Member Functions inherited from [L4::Epiface\\_t0< void, Epiface >](#)

- [Type\\_info::Demand](#) **get\_buffer\_demand** () const  
*Get the server-side buffer demand based in IFACE.*
- [Cap< void > obj\\_cap](#) () const  
*Get the (typed) capability to this object.*

## Public Member Functions inherited from [L4::Epiface](#)

- **Epiface** ()  
*Make a server object.*
- virtual **~Epiface** ()=0  
*Destroy the object.*
- Stored\_cap [obj\\_cap](#) () const  
*Get the capability to the kernel object belonging to this object.*
- [Server\\_iface](#) \* [server\\_iface](#) () const  
*Get pointer to server interface at which the object is currently registered.*
- int **set\_server** ([Server\\_iface](#) \*srv, [Cap< void > cap](#), bool managed=false)  
*Set server registration info for the object.*
- void **set\_obj\_cap** ([Cap< void > const &cap](#))  
*Deprecated server registration function.*

### 15.431.1 Detailed Description

```
template<typename Rnd_state, typename Epiface = L4virtio::Device>
class L4virtio::Svr::Virtio_rng< Rnd_state, Epiface >::Host_irq
```

Handler for the host irq.

An [L4::lrqep\\_t](#) to handle irq's send to the server.

Definition at line 51 of file [virtio-rng-device](#).

The documentation for this class was generated from the following file:

- [l4/l4virtio/server/virtio-rng-device](#)

## 15.432 L4virtio::Svr::Virtio\_rng< Rnd\_state, Epiface >::Request\_processor Class Reference


Handler for the Virtio requests.

```
#include <virtio-rng-device>
```

Inheritance diagram for L4virtio::Svr::Virtio\_rng< Rnd\_state, Epiface >::Request\_processor:



Collaboration diagram for L4virtio::Svr::Virtio\_rng< Rnd\_state, Epiface >::Request\_processor:



### Additional Inherited Members

### Public Member Functions inherited from [L4virtio::Svr::Request\\_processor](#)

- `template<typename DESC_MAN, typename ... ARGS>`  
`void start (DESC_MAN *dm, Virtqueue *ring, Virtqueue::Head\_desc const &request, ARGS... args)`  
*Start processing a new request.*
- `template<typename DESC_MAN, typename ... ARGS>`  
`Virtqueue::Request const & start (DESC_MAN *dm, Virtqueue::Request const &request, ARGS... args)`  
*Start processing a new request.*
- `Virtqueue::Desc::Flags current\_flags () const`  
*Get the flags of the currently processed descriptor.*
- `bool has\_more () const`  
*Are there more chained descriptors?*
- `template<typename DESC_MAN, typename ... ARGS>`  
`bool next (DESC_MAN *dm, ARGS... args)`  
*Switch to the next descriptor in a descriptor chain.*



### 15.432.1 Detailed Description

```
template<typename Rnd_state, typename Epiface = L4virtio::Device>  
class L4virtio::Svr::Virtio_rng< Rnd_state, Epiface >::Request_processor
```

Handler for the Virtio requests.

Definition at line 68 of file [virtio-rng-device](#).

The documentation for this class was generated from the following file:


- I4/I4virtio/server/virtio-rng-device

## 15.433 L4virtio::Svr::Virtio\_spi< Spi\_request\_handler, Epiface > Class Template Reference


A server implementation of the virtio-spi protocol.

```
#include <virtio-spi-device>
```

Inheritance diagram for L4virtio::Svr::Virtio\_spi< Spi\_request\_handler, Epiface >:



Collaboration diagram for L4virtio::Svr::Virtio\_spi< Spi\_request\_handler, Epiface >:



## Data Structures

- class [Host\\_irq](#)  
Handler for the host IRQ.
- class [Request\\_processor](#)  
Handler for the Virtio requests.

## Public Member Functions

- void **reset** () override  
*reset callback, called for doing a device reset*
- bool **check\_queues** () override  
*callback for checking if the queues at DRIVER\_OK transition*
- int **reconfig\_queue** (unsigned idx) override  
*callback for client queue-config request*
- void **trigger\_driver\_config\_irq** () override  
*callback for triggering configuration change notification IRQ*
- [L4::Cap](#) < [L4::Irq](#) > **device\_notify\_irq** () const override  
*callback to gather the device notification IRQ (old-style)*
- void **register\_single\_driver\_irq** () override  
*callback for registering a single guest IRQ for all queues (old-style)*

## Public Member Functions inherited from [L4virtio::Svr::Device\\_t](#) < [No\\_custom\\_data](#) >

- virtual bool **check\_features** ()  
*callback for checking the subset of accepted features*
- virtual void **cfg\_changed** (unsigned)  
*callback for client device configuration changes*
- virtual void **register\_driver\_irq** (unsigned idx)  
*Callback for registering an notification IRQ (multi IRQ).*
- virtual [L4::Cap](#) < [L4::Irq](#) > **device\_notify\_irq** (unsigned idx)  
*Callback to gather the device notification IRQ (multi IRQ).*
- virtual unsigned **num\_events\_supported** () const  
*Return the highest notification index supported.*
- **Device\_t** ([Dev\\_config](#) \*dev\_config)  
*Make a device for the given config.*
- Mem\_list const \* **mem\_info** () const  
*Get the memory region list used for this device.*
- void **reset\_queue\_config** (unsigned idx, unsigned num\_max, bool inc\_generation=false, unsigned device\_notify\_index=0)  
*Trigger reset for the configuration space for queue idx.*
- void **init\_mem\_info** (unsigned num)  
*Initialize the memory region list to the given maximum.*
- void **device\_error** ()  
*Transition device into DEVICE\_NEEDS\_RESET state.*
- bool **setup\_queue** (Virtqueue \*q, unsigned qn, unsigned num\_max)  
*Enable/disable the specified queue.*
- bool **handle\_mem\_cmd\_write** ()  
*Check for a value in the cmd register and handle a write.*
- void **enable\_trusted\_ds\_validation** ()  
*Enable trusted dataspace validation.*
- void **add\_trusted\_dataspaces** (std::shared\_ptr < [Ds\\_vector](#) const > ds)  
*Provide a list of trusted dataspaces that can be used for validation.*

**Public Member Functions inherited from L4::Epiface\_t0< L4virtio::Device, L4::Epiface >**

- [Type\\_info::Demand](#) **get\_buffer\_demand** () const  
*Get the server-side buffer demand based in IFACE.*
- [Cap< L4virtio::Device >](#) **obj\_cap** () const  
*Get the (typed) capability to this object.*

**Public Member Functions inherited from L4::Epiface**

- **Epiface** ()  
*Make a server object.*
- virtual **~Epiface** ()=0  
*Destroy the object.*
- Stored\_cap [obj\\_cap](#) () const  
*Get the capability to the kernel object belonging to this object.*
- [Server\\_iface](#) \* **server\_iface** () const  
*Get pointer to server interface at which the object is currently registered.*
- int **set\_server** ([Server\\_iface](#) \*srv, [Cap< void >](#) cap, bool managed=false)  
*Set server registration info for the object.*
- void **set\_obj\_cap** ([Cap< void >](#) const &cap)  
*Deprecated server registration function.*

**Additional Inherited Members****Public Types inherited from L4::Epiface\_t0< L4virtio::Device, L4::Epiface >**

- typedef [L4virtio::Device](#) **Interface**  
*Data type of the IPC interface definition.*

**Public Types inherited from L4::Epiface**

- typedef [lpc\\_svr::Server\\_iface](#) **Server\_iface**  
*Type for abstract server interface.*
- typedef [lpc\\_svr::Server\\_iface::Demand](#) **Demand**  
*Type for server-side receive buffer demand.*

**Protected Attributes inherited from L4virtio::Svr::Device\_t< No\_custom\_data >**

- **Mem\_list\_mem\_info**  
*Memory region list.*

### 15.433.1 Detailed Description

```
template<typename Spi_request_handler, typename Epiface = L4virtio::Device>
class L4virtio::Svr::Virtio_spi< Spi_request_handler, Epiface >
```

A server implementation of the virtio-spi protocol.

#### Template Parameters

<i>Spi_request_handler</i>	The type that is used to handle incoming requests. Needs to have: <ul style="list-style-type: none"> <li>• <code>handle_transfer(Spi_transfer_head const &amp;, <a href="#">l4_uint8_t</a> const *, <a href="#">l4_uint8_t</a> *, unsigned) function.</code></li> </ul>
<i>Epiface</i>	The Epiface to derive from. Defaults to <a href="#">L4virtio::Device</a> .

Definition at line [101](#) of file [virtio-spi-device](#).

The documentation for this class was generated from the following file:


- [l4/l4virtio/server/virtio-spi-device](#)

## 15.434 L4virtio::Svr::Virtio\_spi< Spi\_request\_handler, Epiface >::Host\_irq Class Reference


Handler for the host IRQ.

```
#include <virtio-spi-device>
```

Inheritance diagram for L4virtio::Svr::Virtio\_spi< Spi\_request\_handler, Epiface >::Host\_irq:



Collaboration diagram for L4virtio::Svr::Virtio\_spi< Spi\_request\_handler, Epiface >::Host\_irq:



### Additional Inherited Members

### Public Types inherited from **L4::Epiface\_t0< void, Epiface >**

- typedef void **Interface**

*Data type of the IPC interface definition.*



## Public Types inherited from L4::Epiface

- typedef [lpc\\_svr::Server\\_iface](#) **Server\_iface**  
*Type for abstract server interface.*
- typedef [lpc\\_svr::Server\\_iface::Demand](#) **Demand**  
*Type for server-side receive buffer demand.*

## Public Member Functions inherited from L4::lrqep\_t< Host\_irq >

- [Cap< L4::lrq >](#) **obj\_cap** () const  
*Get the (typed) capability to this object.*

## Public Member Functions inherited from L4::Epiface\_t0< void, Epiface >

- [Type\\_info::Demand](#) **get\_buffer\_demand** () const  
*Get the server-side buffer demand based in IFACE.*
- [Cap< void >](#) **obj\_cap** () const  
*Get the (typed) capability to this object.*

## Public Member Functions inherited from L4::Epiface

- **Epiface** ()  
*Make a server object.*
- virtual **~Epiface** ()=0  
*Destroy the object.*
- Stored\_cap **obj\_cap** () const  
*Get the capability to the kernel object belonging to this object.*
- [Server\\_iface](#) \* **server\_iface** () const  
*Get pointer to server interface at which the object is currently registered.*
- int **set\_server** ([Server\\_iface](#) \*srv, [Cap< void >](#) cap, bool managed=false)  
*Set server registration info for the object.*
- void **set\_obj\_cap** ([Cap< void >](#) const &cap)  
*Deprecated server registration function.*

### 15.434.1 Detailed Description

```
template<typename Spi_request_handler, typename Epiface = L4virtio::Device>
class L4virtio::Svr::Virtio_spi< Spi_request_handler, Epiface >::Host_irq
```

Handler for the host IRQ.

An [L4::lrqep\\_t](#) to handle irq's send to the server.

Definition at line 118 of file [virtio-spi-device](#).

The documentation for this class was generated from the following file:


- I4/I4virtio/server/virtio-spi-device

## 15.435 L4virtio::Svr::Virtio\_spi< Spi\_request\_handler, Epiface >::Request\_processor Class Reference


Handler for the Virtio requests.

```
#include <virtio-spi-device>
```

Inheritance diagram for L4virtio::Svr::Virtio\_spi< Spi\_request\_handler, Epiface >::Request\_processor:



Collaboration diagram for L4virtio::Svr::Virtio\_spi< Spi\_request\_handler, Epiface >::Request\_processor:



## Public Member Functions

- Spi\_transfer\_req [get\\_request](#) ()

*Linux prepares the SPI request in three or four data parts: 1st: transfer\_head 2nd: TX buffer (not present for RX half-duplex transfers) 3rd: RX buffer (not present for TX half-duplex transfers) 4th: transfer result.*

## Public Member Functions inherited from [L4virtio::Svr::Request\\_processor](#)

- template<typename DESC\_MAN, typename ... ARGS>  
void [start](#) (DESC\_MAN \*dm, Virtqueue \*ring, [Virtqueue::Head\\_desc](#) const &request, ARGS... args)  
*Start processing a new request.*
- template<typename DESC\_MAN, typename ... ARGS>  
Virtqueue::Request const & [start](#) (DESC\_MAN \*dm, Virtqueue::Request const &request, ARGS... args)  
*Start processing a new request.*
- [Virtqueue::Desc::Flags](#) [current\\_flags](#) () const  
*Get the flags of the currently processed descriptor.*
- bool [has\\_more](#) () const  
*Are there more chained descriptors?*
- template<typename DESC\_MAN, typename ... ARGS>  
bool [next](#) (DESC\_MAN \*dm, ARGS... args)  
*Switch to the next descriptor in a descriptor chain.*

### 15.435.1 Detailed Description

```
template<typename Spi_request_handler, typename Epiface = L4virtio::Device>
class L4virtio::Svr::Virtio_spi< Spi_request_handler, Epiface >::Request_processor
```

Handler for the Virtio requests.

Definition at line 135 of file [virtio-spi-device](#).

### 15.435.2 Member Function Documentation

#### 15.435.2.1 get\_request()

```
template<typename Spi_request_handler, typename Epiface = L4virtio::Device>
Spi_transfer_req L4virtio::Svr::Virtio_spi< Spi_request_handler, Epiface >::Request_processor↔
::get_request () [inline]
```


Linux prepares the SPI request in three or four data parts: 1st: transfer\_head 2nd: TX buffer (not present for RX half-duplex transfers) 3rd: RX buffer (not present for TX half-duplex transfers) 4th: transfer result.

This parses the three/four Data\_buffers and recreates the virtio\_spi\_transfer\_req structure.

Definition at line 185 of file [virtio-spi-device](#).

References [L4virtio::Svr::Request\\_processor::current\\_flags\(\)](#), [L4virtio::Svr::Request\\_processor::has\\_more\(\)](#), [L4\\_EIO](#), [L4virtio::Svr::Request\\_processor::next\(\)](#), and [L4Re::throw\\_error\(\)](#).

Here is the call graph for this function:



The documentation for this class was generated from the following file:


- [l4/l4virtio/server/virtio-spi-device](#)

## 15.436 L4virtio::Svr::Virtqueue Class Reference


[Virtqueue](#) implementation for the device.

```
#include <virtio>
```

Inheritance diagram for L4virtio::Svr::Virtqueue:



Collaboration diagram for L4virtio::Svr::Virtqueue:



## Data Structures

- class [Head\\_desc](#)  
*VIRTIO request, essentially a descriptor from the available ring.*

## Public Member Functions

- Request [next\\_avail](#) ()

- Get the next available descriptor from the available ring.*

    - void `rewind_avail` (`Head_desc` const &d)

*Return unfinished descriptors to the available ring, i.e.*

  - bool `desc_avail` () const
- Test for available descriptors.*

    - void `consumed` (`Head_desc` const &r, `l4_uint32_t` len=0)

*Put the given descriptor into the used ring.*

  - template<typename ITER>  
void `consumed` (ITER const &begin, ITER const &end)
- Put multiple descriptors into the used ring.*

  - template<typename QUEUE\_OBSERVER>  
void `finish` (`Head_desc` &d, QUEUE\_OBSERVER \*o, `l4_uint32_t` len=0)
- Add a descriptor to the used ring, and notify an observer.*

  - template<typename ITER, typename QUEUE\_OBSERVER>  
void `finish` (ITER const &begin, ITER const &end, QUEUE\_OBSERVER \*o)
- Add a range of descriptors to the used ring, and notify an observer once.*

  - void `disable_notify` ()
- Set the 'no notify' flag for this queue.*

  - void `enable_notify` ()
- Clear the 'no notify' flag for this queue.*

  - `Desc` const \* `desc` (unsigned idx) const
- Get a descriptor from the descriptor list.*

## Public Member Functions inherited from L4virtio::Virtqueue

- void `disable` ()
- Completely disable the queue.*

  - unsigned long `total_size` () const
- Calculate the total size of this virtqueue.*

  - unsigned long `avail_offset` () const
- Get the offset of the available ring from the descriptor table.*

  - unsigned long `used_offset` () const
- Get the offset of the used ring from the descriptor table.*

  - void `setup` (unsigned num, void \*desc, void \*avail, void \*used)
- Enable this queue.*

  - void `setup_simple` (unsigned num, void \*ring)
- Enable this queue.*

  - void `dump` (`Desc` const \*d) const
- Dump descriptors for this queue.*

  - bool `ready` () const
- Test if this queue is in working state.*

  - unsigned num () const
- Get the no IRQ flag of this queue.*

  - bool `no_notify_guest` () const
- Get the no notify flag of this queue.*

  - bool `no_notify_host` () const
- Get the no notify flag of this queue.*

  - void `no_notify_host` (bool value)
- Set the no-notify flag for this queue.*

  - `l4_uint16_t` `get_avail_idx` () const
- Get available index from available ring (for debugging).*

  - `l4_uint16_t` `get_tail_avail_idx` () const
- Get tail-available index stored in local state (for debugging).*

## Additional Inherited Members

### Public Types inherited from [L4virtio::Virtqueue](#)

- `enum`  
*Fixed alignment values for different parts of a virtqueue.*

### Static Public Member Functions inherited from [L4virtio::Virtqueue](#)

- static unsigned long `total_size` (unsigned `num`)  
*Calculate the total size for a virtqueue of the given dimensions.*
- static unsigned long `desc_size` (unsigned `num`)  
*Calculate the size of the descriptor table for `num` entries.*
- static unsigned long `desc_align` ()  
*Get the alignment in zero LSBs needed for the descriptor table.*
- static unsigned long `avail_size` (unsigned `num`)  
*Calculate the size of the available ring for `num` entries.*
- static unsigned long `avail_align` ()  
*Get the alignment in zero LSBs needed for the available ring.*
- static unsigned long `used_size` (unsigned `num`)  
*Calculate the size of the used ring for `num` entries.*
- static unsigned long `used_align` ()  
*Get the alignment in zero LSBs needed for the used ring.*

### Protected Member Functions inherited from [L4virtio::Virtqueue](#)

- `Virtqueue ()`=default  
*Create a disabled virtqueue.*

### Protected Attributes inherited from [L4virtio::Virtqueue](#)

- `Desc * _desc` = nullptr  
*pointer to descriptor table, NULL if queue is off.*
- `Avail * _avail` = nullptr  
*pointer to available ring.*
- `Used * _used` = nullptr  
*pointer to used ring.*
- `l4_uint16_t _current_avail` = 0  
*The life counter for the queue.*
- `l4_uint16_t _idx_mask` = 0  
*mask used for indexing into the descriptor table and the rings.*

## 15.436.1 Detailed Description

[Virtqueue](#) implementation for the device.

This class represents a single virtqueue, with a local running available index.

#### Note

The [Virtqueue](#) implementation is not thread-safe.

Definition at line 87 of file [virtio](#).



## 15.436.2 Member Function Documentation

### 15.436.2.1 consumed() [1/2]

```
void L4virtio::Svr::Virtqueue::consumed (
    Head_desc const & r,
    14_uint32_t len = 0) [inline]
```

Put the given descriptor into the used ring.

#### Parameters

<i>r</i>	Request that shall be marked as finished.
<i>len</i>	The total number of bytes written.

#### Precondition

queue must be in working state.


*r* must be a valid request from this queue.

Definition at line 190 of file [virtio](#).

References [L4virtio::Virtqueue::\\_desc](#), [L4virtio::Virtqueue::\\_idx\\_mask](#), and [L4virtio::Virtqueue::\\_used](#).

Referenced by [finish\(\)](#), and [finish\(\)](#).

Here is the caller graph for this function:



### 15.436.2.2 consumed() [2/2]

```
template<typename ITER>
void L4virtio::Svr::Virtqueue::consumed (
    ITER const & begin,
    ITER const & end) [inline]
```

Put multiple descriptors into the used ring.

A range of descriptors, specified by *begin* and *end* iterators is added. Each iterator points to a struct that has a *first* member that is a [Head\\_desc](#) and a *second* member that is the corresponding number of bytes written.

#### Template Parameters

<i>ITER</i>	The type of the iterator (inferred).
-------------	--------------------------------------

#### Parameters

<i>begin</i>	Iterator pointing to first new descriptor.
<i>end</i>	Iterator pointing to one past last entry.

#### Precondition

queue must be in working state.

Definition at line 213 of file [virtio](#).

References [L4virtio::Virtqueue::\\_desc](#), [L4virtio::Virtqueue::\\_idx\\_mask](#), and [L4virtio::Virtqueue::\\_used](#).

### 15.436.2.3 desc()

```
Desc const * L4virtio::Svr::Virtqueue::desc (
    unsigned idx) const [inline]
```

Get a descriptor from the descriptor list.

#### Parameters

<i>idx</i>	The index of the descriptor.
------------	------------------------------

### Precondition

```
idx < num
```


queue must be in working state

Definition at line 298 of file virtio.

References [L4virtio::Virtqueue::\\_desc](#).

Referenced by [L4virtio::Svr::Request\\_processor::start\(\)](#).

Here is the caller graph for this function:



#### 15.436.2.4 desc\_avail()

```
bool L4virtio::Svr::Virtqueue::desc_avail () const [inline]
```

Test for available descriptors.

## Returns

true if there are descriptors available, false if not.

**Precondition**


The queue must be in working state.

Definition at line 175 of file [virtio](#).

References [L4virtio::Virtqueue::\\_avail](#), and [L4virtio::Virtqueue::\\_current\\_avail](#).

Referenced by [Virtio\\_net\\_request::drop\\_requests\(\)](#), and [L4virtio\\_port::tx\\_work\\_pending\(\)](#).

Here is the caller graph for this function:

**15.436.2.5 disable\_notify()**

```
void L4virtio::Svr::Virtqueue::disable_notify () [inline]
```

Set the 'no notify' flag for this queue.


This function may be called on a disabled queue.

Definition at line 273 of file [virtio](#).


References [L4virtio::Virtqueue::\\_used](#), [L4\\_LIKELY](#), and [L4virtio::Virtqueue::ready\(\)](#).

Referenced by [Virtio\\_switch::handle\\_l4virtio\\_port\\_tx\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



**15.436.2.6 enable\_notify()**

```
void L4virtio::Svr::Virtqueue::enable_notify () [inline]
```

Clear the 'no notify' flag for this queue.


This function may be called on a disabled queue.

Definition at line 284 of file [virtio](#).

References [L4virtio::Virtqueue::\\_used](#), [L4\\_LIKELY](#), and [L4virtio::Virtqueue::ready\(\)](#).

Referenced by [Virtio\\_switch::handle\\_l4virtio\\_port\\_tx\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:

**15.436.2.7 finish() [1/2]**

```
template<typename QUEUE_OBSERVER>
void L4virtio::Svr::Virtqueue::finish (
    Head_desc & d,
    QUEUE_OBSERVER * o,
    l4_uint32_t len = 0) [inline]
```

Add a descriptor to the used ring, and notify an observer.

**Template Parameters**

<code>QUEUE_OBSERVER</code>	The type of the observer (inferred).
-----------------------------	--------------------------------------

### Parameters

<i>d</i>	descriptor of the request that is to be marked as finished.
<i>o</i>	Pointer to the observer that is notified.
<i>len</i>	Number of bytes written for this request.

### Precondition

queue must be in working state.


*d* must be a valid request from this queue.

Definition at line 240 of file [virtio](#).


References [consumed\(\)](#).

Referenced by [Virtio\\_net\\_request::drop\\_requests\(\)](#), [L4virtio::Svr::Console::Virtio\\_con::handle\\_control\\_message\(\)](#), [L4virtio::Svr::Console::Device::port\\_read\(\)](#), [L4virtio::Svr::Console::Device::port\\_write\(\)](#), and [L4virtio::Svr::Console::Virtio\\_con::send\\_control\\_message\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



**15.436.2.8 finish() [2/2]**

```
template<typename ITER, typename QUEUE_OBSERVER>
void L4virtio::Svr::Virtqueue::finish (
    ITER const & begin,
    ITER const & end,
    QUEUE_OBSERVER * o) [inline]
```

Add a range of descriptors to the used ring, and notify an observer once.

The iterators are passed to [consumed<ITER>\(ITER const &, ITER const &\)](#), and the requirements detailed there apply.

**Template Parameters**

<i>ITER</i>	type of the iterator (inferred)
<i>QUEUE_OBSERVER</i>	the type of the observer (inferred).

**Parameters**

<i>begin</i>	iterator pointing to first element.
<i>end</i>	iterator pointing to one past last element.
<i>o</i>	pointer to the observer that is notified.


**Precondition**

queue must be in working state.

Definition at line [262](#) of file [virtio](#).

References [consumed\(\)](#).

Here is the call graph for this function:



### 15.436.2.9 next\_avail()

```
Request L4virtio::Svr::Virtqueue::next_avail () [inline]
```

Get the next available descriptor from the available ring.

#### Precondition

The queue must be in working state.

#### Returns

A Request for the next available descriptor, the Request is invalid if there are no descriptors in the available ring.

#### Note


The return value must be checked even when a previous [desc\\_avail\(\)](#) returned true.

Definition at line 136 of file [virtio](#).

References [L4virtio::Virtqueue::\\_avail](#), [L4virtio::Virtqueue::\\_current\\_avail](#), [L4virtio::Virtqueue::\\_idx\\_mask](#), and [L4\\_LIKELY](#).

Referenced by [Virtio\\_net\\_request::drop\\_requests\(\)](#), [Virtio\\_net\\_request::get\\_request\(\)](#), [L4virtio::Svr::Console::Virtio\\_con::handle\\_control\\_message](#), [L4virtio::Svr::Console::Device::port\\_read\(\)](#), [L4virtio::Svr::Console::Device::port\\_write\(\)](#), and [L4virtio::Svr::Console::Virtio\\_con::send\\_control\\_message](#).

Here is the caller graph for this function:





## 15.436.2.10 rewind\_avail()

```
void L4virtio::Svr::Virtqueue::rewind_avail (
    Head_desc const & d) [inline]
```

Return unfinished descriptors to the available ring, i.e.

reset the local next index of the available ring to the given descriptor.

## Parameters

<i>d</i>	descriptor of the request that is to be marked as finished.
----------	---

## Precondition

queue must be in working state.

*d* must be a valid request from this queue, obtained via [next\\_avail\(\)](#), that has not yet been finished, and in addition, no descriptors following it have been finished.

Definition at line 160 of file [virtio](#).

References [L4virtio::Virtqueue::\\_current\\_avail](#), [L4virtio::Virtqueue::\\_desc](#), and [L4virtio::Virtqueue::\\_idx\\_mask](#).

The documentation for this class was generated from the following file:


- I4/I4virtio/server/virtio

## 15.437 L4virtio::Svr::Virtqueue::Head\_desc Class Reference

VIRTIO request, essentially a descriptor from the available ring.

```
#include <virtio>
```

Collaboration diagram for L4virtio::Svr::Virtqueue::Head\_desc:



## Public Member Functions

- **Head\_desc** ()  
*Make invalid (NULL) request.*
- bool **valid** () const
- **operator bool** () const
- **Desc** const \* **desc** () const

### 15.437.1 Detailed Description

VIRTIO request, essentially a descriptor from the available ring.

Definition at line 93 of file [virtio](#).

### 15.437.2 Member Function Documentation

#### 15.437.2.1 desc()

```
Desc const * L4virtio::Svr::Virtqueue::Head_desc::desc () const [inline]
```


#### Returns

Pointer to the head descriptor of the request.

Definition at line 112 of file [virtio](#).

Referenced by [L4virtio::Svr::Request\\_processor::start\(\)](#).

Here is the caller graph for this function:



### 15.437.2.2 operator bool()

```
L4virtio::Svr::Virtqueue::Head_desc::operator bool () const [inline], [explicit]
```

#### Returns

True if the request is valid (not NULL).

Definition at line 108 of file [virtio](#).

References [valid\(\)](#).

Here is the call graph for this function:



### 15.437.2.3 valid()

```
bool L4virtio::Svr::Virtqueue::Head_desc::valid () const [inline]
```


#### Returns

True if the request is valid (not NULL).

Definition at line 105 of file [virtio](#).

Referenced by [operator bool\(\)](#), and [L4virtio::Svr::Console::Device::port\\_read\(\)](#).

Here is the caller graph for this function:



The documentation for this class was generated from the following file:

- `I4/I4virtio/server/virtio`

## 15.438 L4virtio::Virtqueue Class Reference


Low-level [Virtqueue](#).

```
#include <virtqueue>
```

Inheritance diagram for L4virtio::Virtqueue:



Collaboration diagram for L4virtio::Virtqueue:



## Data Structures

- class [Desc](#)  
*Descriptor in the descriptor table.*
- class [Avail](#)  
*Type of available ring, this is read-only for the host.*
- struct [Used\\_elem](#)

*Type of an element of the used ring.*

- class [Used](#)  
*Used ring.*

## Public Types

- enum  
*Fixed alignment values for different parts of a virtqueue.*

## Public Member Functions

- void [disable](#) ()  
*Completely disable the queue.*
- unsigned long [total\\_size](#) () const  
*Calculate the total size of this virtqueue.*
- unsigned long [avail\\_offset](#) () const  
*Get the offset of the available ring from the descriptor table.*
- unsigned long [used\\_offset](#) () const  
*Get the offset of the used ring from the descriptor table.*
- void [setup](#) (unsigned [num](#), void \*desc, void \*avail, void \*used)  
*Enable this queue.*
- void [setup\\_simple](#) (unsigned [num](#), void \*ring)  
*Enable this queue.*
- void [dump](#) ([Desc](#) const \*d) const  
*Dump descriptors for this queue.*
- bool [ready](#) () const  
*Test if this queue is in working state.*
- unsigned [num](#) () const
- bool [no\\_notify\\_guest](#) () const  
*Get the no IRQ flag of this queue.*
- bool [no\\_notify\\_host](#) () const  
*Get the no notify flag of this queue.*
- void [no\\_notify\\_host](#) (bool value)  
*Set the no-notify flag for this queue.*
- [l4\\_uint16\\_t](#) [get\\_avail\\_idx](#) () const  
*Get available index from available ring (for debugging).*
- [l4\\_uint16\\_t](#) [get\\_tail\\_avail\\_idx](#) () const  
*Get tail-available index stored in local state (for debugging).*

## Static Public Member Functions

- static unsigned long [total\\_size](#) (unsigned [num](#))  
*Calculate the total size for a virtqueue of the given dimensions.*
- static unsigned long [desc\\_size](#) (unsigned [num](#))  
*Calculate the size of the descriptor table for [num](#) entries.*
- static unsigned long [desc\\_align](#) ()  
*Get the alignment in zero LSBs needed for the descriptor table.*
- static unsigned long [avail\\_size](#) (unsigned [num](#))  
*Calculate the size of the available ring for [num](#) entries.*
- static unsigned long [avail\\_align](#) ()  
*Get the alignment in zero LSBs needed for the available ring.*
- static unsigned long [used\\_size](#) (unsigned [num](#))  
*Calculate the size of the used ring for [num](#) entries.*
- static unsigned long [used\\_align](#) ()  
*Get the alignment in zero LSBs needed for the used ring.*

## Protected Member Functions

- **Virtqueue** ()=default  
*Create a disabled virtqueue.*

## Protected Attributes

- **Desc** \* **\_desc** = nullptr  
*pointer to descriptor table, NULL if queue is off.*
- **Avail** \* **\_avail** = nullptr  
*pointer to available ring.*
- **Used** \* **\_used** = nullptr  
*pointer to used ring.*
- **l4\_uint16\_t** **\_current\_avail** = 0  
*The life counter for the queue.*
- **l4\_uint16\_t** **\_idx\_mask** = 0  
*mask used for indexing into the descriptor table and the rings.*

## 15.438.1 Detailed Description

Low-level [Virtqueue](#).

This class represents a single virtqueue, with a local running available index.

### Note

The [Virtqueue](#) implementation is not thread-safe.

Definition at line 80 of file [virtqueue](#).

## 15.438.2 Member Function Documentation

### 15.438.2.1 `avail_align()`

```
unsigned long L4virtio::Virtqueue::avail_align () [inline], [static]
```

Get the alignment in zero LSBs needed for the available ring.

### Returns

The alignment in zero LSBs needed for an available ring.

Definition at line 287 of file [virtqueue](#).

### 15.438.2.2 avail\_size()

```
unsigned long L4virtio::Virtqueue::avail_size (
    unsigned num) [inline], [static]
```

Calculate the size of the available ring for `num` entries.

#### Parameters

<code>num</code>	The number of entries in the available ring.
------------------	--

#### Returns

The size in bytes needed for an available ring with `num` entries.

Definition at line 279 of file `virtqueue`.


References `num()`.

Referenced by `L4virtio::Svr::Device_t< No_custom_data >::setup_queue()`, `setup_simple()`, and `total_size()`.

Here is the call graph for this function:



Here is the caller graph for this function:





### 15.438.2.3 desc\_align()

```
unsigned long L4virtio::Virtqueue::desc_align () [inline], [static]
```

Get the alignment in zero LSBs needed for the descriptor table.

#### Returns

The alignment in zero LSBs needed for a descriptor table.

Definition at line 269 of file [virtqueue](#).

### 15.438.2.4 desc\_size()

```
unsigned long L4virtio::Virtqueue::desc_size (  
    unsigned num) [inline], [static]
```

Calculate the size of the descriptor table for [num](#) entries.

#### Parameters

<i>num</i>	The number of entries in the descriptor table.
------------	--

#### Returns


The size in bytes needed for a descriptor table with [num](#) entries.

Definition at line 261 of file [virtqueue](#).


References [num\(\)](#).

Referenced by [L4virtio::Svr::Device\\_t< No\\_custom\\_data >::setup\\_queue\(\)](#), [setup\\_simple\(\)](#), and [total\\_size\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 15.438.2.5 disable()

```
void L4virtio::Virtqueue::disable () [inline]
```

Completely disable the queue.


[setup\(\)](#) must be used to enable the queue again.

Definition at line 224 of file [virtqueue](#).

References [\\_desc](#).

Referenced by [L4virtio::Svr::Device\\_t< No\\_custom\\_data >::setup\\_queue\(\)](#).

Here is the caller graph for this function:



### 15.438.2.6 dump()

```
void L4virtio::Virtqueue::dump (
    Desc const * d) const [inline]
```

Dump descriptors for this queue.


#### Precondition

the queue must be in working state.

Definition at line 392 of file [virtqueue](#).

References [\\_desc](#), and [L4virtio::Virtqueue::Desc::dump\(\)](#).

Here is the call graph for this function:



### 15.438.2.7 `get_avail_idx()`

```
l4_uint16_t L4virtio::Virtqueue::get_avail_idx () const [inline]
```

Get available index from available ring (for debugging).

#### Precondition

Queue must be in a working state.

#### Returns

current index in the available ring (shared between device model and device driver).

Definition at line 449 of file [virtqueue](#).

References [\\_avail](#).

### 15.438.2.8 `get_tail_avail_idx()`

```
l4_uint16_t L4virtio::Virtqueue::get_tail_avail_idx () const [inline]
```

Get tail-available index stored in local state (for debugging).

#### Returns

current tail index for the the available ring.

Definition at line 456 of file [virtqueue](#).

References [\\_current\\_avail](#).

### 15.438.2.9 `no_notify_guest()`

```
bool L4virtio::Virtqueue::no_notify_guest () const [inline]
```

Get the no IRQ flag of this queue.

#### Precondition

queue must be in working state.

**Returns**


true if the guest does not want to get IRQs (currently).

Definition at line 414 of file [virtqueue](#).

References [\\_avail](#).

Referenced by [L4virtio::Svr::Block\\_dev\\_base<Ds\\_data>::finalize\\_request\(\)](#), and [L4virtio::Svr::Console::Device::notify\\_queue\(\)](#).

Here is the caller graph for this function:

**15.438.2.10 no\_notify\_host() [1/2]**

```
bool L4virtio::Virtqueue::no_notify_host () const [inline]
```

Get the no notify flag of this queue.

**Precondition**

queue must be in working state.

**Returns**

true if the host does not want to get IRQs (currently).

Definition at line 426 of file [virtqueue](#).

References [\\_used](#).

**15.438.2.11 no\_notify\_host() [2/2]**

```
void L4virtio::Virtqueue::no_notify_host (
    bool value) [inline]
```

Set the no-notify flag for this queue.

**Precondition**

Queue must be in a working state.

Definition at line 436 of file [virtqueue](#).

References [\\_used](#).



**15.438.2.13 ready()**

```
bool L4virtio::Virtqueue::ready () const [inline]
```

Test if this queue is in working state.

**Returns**


true when the queue is in working state, false else.

Definition at line 400 of file [virtqueue](#).

References [\\_desc](#), and [L4\\_LIKELY](#).

Referenced by [L4virtio::Svr::Virtqueue::disable\\_notify\(\)](#), [Virtio\\_net\\_request::drop\\_requests\(\)](#), [L4virtio::Svr::Virtqueue::enable\\_notify\(\)](#), [Virtio\\_net\\_request::get\\_request\(\)](#), [L4virtio::Svr::Console::Virtio\\_con::handle\\_control\\_message\(\)](#), and [L4virtio::Svr::Console::Virtio\\_con::port\\_name\(\)](#).

Here is the caller graph for this function:

**15.438.2.14 setup()**

```
void L4virtio::Virtqueue::setup (
    unsigned num,
    void * desc,
    void * avail,
    void * used) [inline]
```

Enable this queue.

## Parameters

<i>num</i>	The number of entries in the descriptor table, the available ring, and the used ring (must be a power of 2).
<i>desc</i>	The address of the descriptor table. (Must be <code>Desc_align</code> aligned and at least <code>desc_size(num)</code> bytes in size.)
<i>avail</i>	The address of the available ring. (Must be <code>Avail_align</code> aligned and at least <code>avail_size(num)</code> bytes in size.)
<i>used</i>	The address of the used ring. (Must be <code>Used_align</code> aligned and at least <code>used_size(num)</code> bytes in size.)


Due to the data type of the descriptors, the queue can have a maximum size of  $2^{16}$ .

Definition at line 349 of file `virtqueue`.


References `_avail`, `_current_avail`, `_desc`, `_idx_mask`, `_used`, `L4_EINVAL`, and `num()`.

Referenced by `L4virtio::Driver::Virtqueue::init_queue()`, `L4virtio::Svr::Device_t< No_custom_data >::setup_queue()`, and `setup_simple()`.

Here is the call graph for this function:



Here is the caller graph for this function:





## 15.438.2.15 setup\_simple()

```
void L4virtio::Virtqueue::setup_simple (
    unsigned num,
    void * ring) [inline]
```

Enable this queue.

## Parameters

<i>num</i>	The number of entries in the descriptor table, the available ring, and the used ring (must be a power of 2).
<i>ring</i>	The base address for the queue data structure. The memory block at <i>ring</i> must be at least <code>total_size(num)</code> bytes in size and have an alignment of <code>Desc_align(desc_align())</code> bits.


Due to the data type of the descriptors, the queue can have a maximum size of  $2^{16}$ .

Definition at line 378 of file [virtqueue](#).


References [avail\\_size\(\)](#), [desc\\_size\(\)](#), [l4\\_round\\_size\(\)](#), [num\(\)](#), and [setup\(\)](#).

Referenced by [L4virtio::Driver::Virtqueue::init\\_queue\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



**15.438.2.16 total\_size() [1/2]**

```
unsigned long L4virtio::Virtqueue::total_size () const [inline]
```

Calculate the total size of this virtqueue.


**Precondition**

The queue has been set up.

Definition at line 314 of file [virtqueue](#).

References [\\_desc](#), [\\_used](#), [num\(\)](#), and [used\\_size\(\)](#).

Here is the call graph for this function:

**15.438.2.17 total\_size() [2/2]**

```
unsigned long L4virtio::Virtqueue::total_size (
    unsigned num) [inline], [static]
```

Calculate the total size for a virtqueue of the given dimensions.

**Parameters**

<i>num</i>	The number of entries in the descriptor table, the available ring, and the used ring (must be a power of 2).
------------	--


**Returns**

The total size in bytes of the queue data structures.

Definition at line 245 of file [virtqueue](#).

References [avail\\_size\(\)](#), [desc\\_size\(\)](#), [l4\\_round\\_size\(\)](#), [num\(\)](#), and [used\\_size\(\)](#).

Here is the call graph for this function:



#### 15.438.2.18 `used_align()`

```
unsigned long L4virtio::Virtqueue::used_align () [inline], [static]
```

Get the alignment in zero LSBs needed for the used ring.

##### Returns

The alignment in zero LSBs needed for an used ring.

Definition at line 306 of file [virtqueue](#).

#### 15.438.2.19 `used_size()`

```
unsigned long L4virtio::Virtqueue::used_size (
    unsigned num) [inline], [static]
```

Calculate the size of the used ring for `num` entries.

##### Parameters

<i>num</i>	The number of entries in the used ring.
------------	---

## Returns


The size in bytes needed for an used ring with `num` entries.

Definition at line 298 of file [virtqueue](#).


References [num\(\)](#).

Referenced by [L4virtio::Svr::Device\\_t< No\\_custom\\_data >::setup\\_queue\(\)](#), [total\\_size\(\)](#), and [total\\_size\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



The documentation for this class was generated from the following file:

- `I4/I4virtio/virtqueue`

## 15.439 L4virtio::Virtqueue::Avail Class Reference

Type of available ring, this is read-only for the host.

```
#include <virtqueue>
```

Collaboration diagram for L4virtio::Virtqueue::Avail:



### Data Structures

- struct [Flags](#)  
*Flags of the available ring.*

### Data Fields

- [Flags flags](#)  
*flags of available ring*
- [l4\\_uint16\\_t idx](#)  
*available index written by guest*
- [l4\\_uint16\\_t ring \[\]](#)  
*array of available descriptor indexes.*

### 15.439.1 Detailed Description

Type of available ring, this is read-only for the host.

Definition at line 128 of file [virtqueue](#).

The documentation for this class was generated from the following file:

- [l4/l4virtio/virtqueue](#)

## 15.440 L4virtio::Virtqueue::Avail::Flags Struct Reference

[Flags](#) of the available ring.

```
#include <virtqueue>
```

Collaboration diagram for L4virtio::Virtqueue::Avail::Flags:

L4virtio::Virtqueue ::Avail::Flags
+ raw
+ Flags()
* no_irq_bfm_t
* no_irq()
* no_irq()

### Public Member Functions

- **Flags** ([l4\\_uint16\\_t](#) v)  
*Make [Flags](#) from the raw value.*

### Data Fields

- [l4\\_uint16\\_t](#) raw  
*raw 16bit flags value of the available ring.*
- typedef [cxx::Bitfield](#)< decltype(raw), 0, 0 > no\_irq\_bfm\_t  
*Guest does not want to receive interrupts when requests are finished.*
- constexpr [no\\_irq\\_bfm\\_t::Val](#) no\_irq () const  
*Get the [no\\_irq](#) bits (0 to 0) of raw.*
- constexpr [no\\_irq\\_bfm\\_t::Ref](#) no\_irq ()  
*Get a reference to the [no\\_irq](#) bits (0 to 0) of raw.*

## 15.440.1 Detailed Description

[Flags](#) of the available ring.

Definition at line [134](#) of file [virtqueue](#).

## 15.440.2 Member Typedef Documentation

### 15.440.2.1 no\_irq\_bfm\_t

```
typedef cxx::Bitfield<decltype(raw), 0, 0> L4virtio::Virtqueue::Avail::Flags::no_irq_bfm_t
```

Guest does not want to receive interrupts when requests are finished.

Type to access the [no\\_irq](#) bits (0 to 0) of [raw](#).

Definition at line [143](#) of file [virtqueue](#).

The documentation for this struct was generated from the following file:


- [l4/l4virtio/virtqueue](#)

## 15.441 L4virtio::Virtqueue::Desc Class Reference

Descriptor in the descriptor table.

```
#include <virtqueue>
```

Collaboration diagram for L4virtio::Virtqueue::Desc:



## Data Structures

- struct [Flags](#)  
*Type for descriptor flags.*

## Public Member Functions

- void **dump** (unsigned idx) const



*Dump a single descriptor.*

### Data Fields

- [Ptr](#)< void > **addr**  
*Address stored in descriptor.*
- [l4\\_uint32\\_t](#) **len**  
*Length of described buffer.*
- [Flags](#) **flags**  
*Descriptor flags.*
- [l4\\_uint16\\_t](#) **next**  
*Index of the next chained descriptor.*

### 15.441.1 Detailed Description

Descriptor in the descriptor table.

Definition at line 86 of file [virtqueue](#).

The documentation for this class was generated from the following file:

- l4/l4virtio/virtqueue

## 15.442 L4virtio::Virtqueue::Desc::Flags Struct Reference

Type for descriptor flags.

```
#include <virtqueue>
```

Collaboration diagram for L4virtio::Virtqueue::Desc::Flags:

L4virtio::Virtqueue ::Desc::Flags
+ raw
+ Flags()
* next_bfm_t
* next()
* next()
* write_bfm_t
* write()
* write()
* indirect_bfm_t
* indirect()
* indirect()

## Public Member Functions

- **Flags** ([l4\\_uint16\\_t](#) v)  
*Make [Flags](#) from raw 16bit value.*

## Data Fields

- [l4\\_uint16\\_t](#) **raw**  
*raw flags value of a virtio descriptor.*
- typedef [cxx::Bitfield](#)< decltype([raw](#)), 0, 0 > [next\\_bfm\\_t](#)  
*Part of a descriptor chain which is continued with the next field.*
- constexpr [next\\_bfm\\_t::Val](#) **next** () const  
*Get the [next](#) bits (0 to 0) of [raw](#).*
- constexpr [next\\_bfm\\_t::Ref](#) **next** ()  
*Get a reference to the [next](#) bits (0 to 0) of [raw](#).*
- typedef [cxx::Bitfield](#)< decltype([raw](#)), 1, 1 > [write\\_bfm\\_t](#)  
*Block described by this descriptor is writeable.*
- constexpr [write\\_bfm\\_t::Val](#) **write** () const  
*Get the [write](#) bits (1 to 1) of [raw](#).*
- constexpr [write\\_bfm\\_t::Ref](#) **write** ()  
*Get a reference to the [write](#) bits (1 to 1) of [raw](#).*
- typedef [cxx::Bitfield](#)< decltype([raw](#)), 2, 2 > [indirect\\_bfm\\_t](#)  
*Indirect descriptor, block contains a list of descriptors.*
- constexpr [indirect\\_bfm\\_t::Val](#) **indirect** () const  
*Get the [indirect](#) bits (2 to 2) of [raw](#).*
- constexpr [indirect\\_bfm\\_t::Ref](#) **indirect** ()  
*Get a reference to the [indirect](#) bits (2 to 2) of [raw](#).*

### 15.442.1 Detailed Description

Type for descriptor flags.

Definition at line 92 of file [virtqueue](#).

### 15.442.2 Member Typedef Documentation

#### 15.442.2.1 indirect\_bfm\_t

```
typedef cxx::Bitfield<decltype(raw), 2, 2> L4virtio::Virtqueue::Desc::Flags::indirect\_bfm\_t
```

Indirect descriptor, block contains a list of descriptors.

Type to access the [indirect](#) bits (2 to 2) of [raw](#).

Definition at line 105 of file [virtqueue](#).

### 15.442.2.2 next\_bfm\_t

```
typedef cxx::Bitfield<decltype(raw), 0, 0> L4virtio::Virtqueue::Desc::Flags::next_bfm_t
```

Part of a descriptor chain which is continued with the next field.

Type to access the `next` bits (0 to 0) of `raw`.

Definition at line 101 of file `virtqueue`.

### 15.442.2.3 write\_bfm\_t

```
typedef cxx::Bitfield<decltype(raw), 1, 1> L4virtio::Virtqueue::Desc::Flags::write_bfm_t
```

Block described by this descriptor is writeable.

Type to access the `write` bits (1 to 1) of `raw`.

Definition at line 103 of file `virtqueue`.

The documentation for this struct was generated from the following file:


- `l4/l4virtio/virtqueue`

## 15.443 L4virtio::Virtqueue::Used Class Reference

`Used` ring.

```
#include <virtqueue>
```

Collaboration diagram for L4virtio::Virtqueue::Used:



## Data Structures

- struct [Flags](#)  
*flags for the used ring.*

## Data Fields

- [Flags](#) **flags**  
*flags of the used ring.*
- [l4\\_uint16\\_t](#) **idx**  
*index of the last entry in the ring.*
- [Used\\_elem](#) **ring** []  
*array of used descriptors.*

### 15.443.1 Detailed Description

[Used](#) ring.

Definition at line [173](#) of file [virtqueue](#).

The documentation for this class was generated from the following file:

- [l4/l4virtio/virtqueue](#)

## 15.444 L4virtio::Virtqueue::Used::Flags Struct Reference

flags for the used ring.

```
#include <virtqueue>
```

Collaboration diagram for L4virtio::Virtqueue::Used::Flags:

L4virtio::Virtqueue ::Used::Flags
+ raw
+ Flags()
* no_notify_bfm_t
* no_notify()
* no_notify()

## Public Member Functions

- **Flags** ([l4\\_uint16\\_t](#) v)  
*make [Flags](#) from raw value*

## Data Fields

- [l4\\_uint16\\_t](#) **raw**  
*raw flags value as specified by virtio.*
- typedef [cxx::Bitfield](#)< decltype([raw](#)), 0, 0 > **no\_notify\_bfm\_t**  
*host does not want to be notified when new requests have been queued.*
- constexpr [no\\_notify\\_bfm\\_t::Val](#) **no\_notify** () const  
*Get the [no\\_notify](#) bits (0 to 0) of [raw](#).*
- constexpr [no\\_notify\\_bfm\\_t::Ref](#) **no\_notify** ()  
*Get a reference to the [no\\_notify](#) bits (0 to 0) of [raw](#).*

### 15.444.1 Detailed Description

flags for the used ring.

Definition at line 179 of file [virtqueue](#).

### 15.444.2 Member Typedef Documentation

#### 15.444.2.1 no\_notify\_bfm\_t

```
typedef cxx::Bitfield<decltype(raw), 0, 0> L4virtio::Virtqueue::Used::Flags::no\_notify\_bfm\_t
```

host does not want to be notified when new requests have been queued.

Type to access the [no\\_notify](#) bits (0 to 0) of [raw](#).

Definition at line 188 of file [virtqueue](#).

The documentation for this struct was generated from the following file:

- [l4/l4virtio/virtqueue](#)

## 15.445 L4virtio::Virtqueue::Used\_elem Struct Reference

Type of an element of the used ring.

```
#include <virtqueue>
```

Collaboration diagram for L4virtio::Virtqueue::Used\_elem:

L4virtio::Virtqueue ::Used_elem
+ id
+ len
+ Used_elem()

### Public Member Functions

- [Used\\_elem](#) ([l4\\_uint16\\_t](#) id, [l4\\_uint32\\_t](#) len)  
*Initialize a used ring element.*

### Data Fields

- [l4\\_uint32\\_t](#) id  
*descriptor index*
- [l4\\_uint32\\_t](#) len  
*length field*

### 15.445.1 Detailed Description

Type of an element of the used ring.

Definition at line [154](#) of file [virtqueue](#).

## 15.445.2 Constructor & Destructor Documentation

### 15.445.2.1 Used\_elem()

```
l4virtio::Virtqueue::Used_elem::Used_elem (
    l4_uint16_t id,
    l4_uint32_t len) [inline]
```

Initialize a used ring element.

#### Parameters

<i>id</i>	The index of the descriptor to be marked as used.
<i>len</i>	The total bytes written into the buffer of the descriptor chain.

Definition at line 165 of file [virtqueue](#).

References [id](#), and [len](#).

The documentation for this struct was generated from the following file:

- l4/l4virtio/virtqueue

## 15.446 l4virtio\_block\_config\_t Struct Reference

Device configuration for block devices.

```
#include <virtio_block.h>
```

Collaboration diagram for l4virtio\_block\_config\_t:



## Data Fields

- [l4\\_uint64\\_t](#) **capacity**  
*Capacity of device in 512-byte sectors.*
- [l4\\_uint32\\_t](#) **size\_max**  
*Maximum size of a single segment.*
- [l4\\_uint32\\_t](#) **seg\_max**  
*Maximum number of segments per request.*
- [l4\\_uint32\\_t](#) **blk\_size**  
*Block size of underlying disk.*

### 15.446.1 Detailed Description

Device configuration for block devices.

Definition at line 68 of file [virtio\\_block.h](#).

The documentation for this struct was generated from the following file:


- [l4/l4virtio/virtio\\_block.h](#)

## 15.447 l4virtio\_block\_discard\_t Struct Reference

Structure used for the write zeroes and discard commands.

```
#include <virtio_block.h>
```

Collaboration diagram for `l4virtio_block_discard_t`:



### 15.447.1 Detailed Description

Structure used for the write zeroes and discard commands.

Definition at line 58 of file [virtio\\_block.h](#).

The documentation for this struct was generated from the following file:

- [l4/l4virtio/virtio\\_block.h](#)



## 15.448 l4virtio\_block\_header\_t Struct Reference

Header structure of a request for a block device.

```
#include <virtio_block.h>
```

Collaboration diagram for l4virtio\_block\_header\_t:

l4virtio_block_header_t	
+	type
+	ioprio
+	sector

### Data Fields

- [l4\\_uint32\\_t](#) **type**  
*Kind of request, see [L4virtio\\_block\\_operations](#).*
- [l4\\_uint32\\_t](#) **ioprio**  
*Priority (unused).*
- [l4\\_uint64\\_t](#) **sector**  
*First sector to read/write.*

### 15.448.1 Detailed Description

Header structure of a request for a block device.

Definition at line 42 of file [virtio\\_block.h](#).

The documentation for this struct was generated from the following file:


- l4/l4virtio/virtio\_block.h

## 15.449 l4virtio\_config\_hdr\_t Struct Reference

L4-VIRTIO config header, provided in shared data space.

```
#include <virtio.h>
```

Collaboration diagram for l4virtio\_config\_hdr\_t:



### Data Fields

- [l4\\_uint32\\_t](#) **magic**  
*magic value (must be 'virt').*
- [l4\\_uint32\\_t](#) **version**  
*VIRTIO version.*
- [l4\\_uint32\\_t](#) **device**  
*device ID*
- [l4\\_uint32\\_t](#) **vendor**  
*vendor ID*
- [l4\\_uint32\\_t](#) **dev\_features**  
*device features windows selected by device\_feature\_sel*
- [l4\\_uint32\\_t](#) **num\_queues**  
*number of virtqueues*
- [l4\\_uint32\\_t](#) **queues\_offset**  
*offset of virtqueue config array*

### 15.449.1 Detailed Description

L4-VIRTIO config header, provided in shared data space.

Definition at line 135 of file [virtio.h](#).

The documentation for this struct was generated from the following file:

- l4/l4virtio/virtio.h

## 15.450 l4virtio\_config\_queue\_t Struct Reference

Queue configuration entry.

```
#include <virtio.h>
```

Collaboration diagram for l4virtio\_config\_queue\_t:

l4virtio_config_queue_t
+ num_max
+ num
+ ready
+ driver_notify_index
+ desc_addr
+ avail_addr
+ used_addr
+ device_notify_index

### Data Fields

- [l4\\_uint16\\_t](#) **num\_max**  
*R: maximum number of descriptors supported by this queue.*
- [l4\\_uint16\\_t](#) **num**  
*RW: number of descriptors configured for this queue.*
- [l4\\_uint16\\_t](#) **ready**  
*RW: queue ready flag (read-write).*
- [l4\\_uint16\\_t](#) **driver\_notify\_index**  
*W: Event index to be used for device notifications (device to driver).*
- [l4\\_uint64\\_t](#) **desc\_addr**  
*W: address of descriptor table.*
- [l4\\_uint64\\_t](#) **avail\_addr**  
*W: address of available ring.*
- [l4\\_uint64\\_t](#) **used\_addr**  
*W: address of used ring.*
- [l4\\_uint16\\_t](#) **device\_notify\_index**  
*R: Event index to be used by the driver (driver to device).*

### 15.450.1 Detailed Description

Queue configuration entry.

An array of such entries is available at the [l4virtio\\_config\\_hdr\\_t::queues\\_offset](#) in the config data space.

Consistency rules for the queue config are:

- A driver might read [num\\_max](#) at any time.
- A driver must write to [num](#), [desc\\_addr](#), [avail\\_addr](#), and [used\\_addr](#) only when [ready](#) is zero (0). Values in these fields are validated and used by the device only after successfully setting [ready](#) to one (1), either by the IPC or by L4VIRTIO\_CMD\_CFG\_QUEUE.
- The value of [device\\_notify\\_index](#) is valid only when [ready](#) is one.
- The driver might write to [device\\_notify\\_index](#) at any time, however the change is guaranteed to take effect after a successful L4VIRTIO\_CMD\_CFG\_QUEUE or after a config\_queue IPC. Note, the change might also have immediate effect, depending on the device implementation.

Definition at line [226](#) of file [virtio.h](#).

The documentation for this struct was generated from the following file:


- [l4/l4virtio/virtio.h](#)

## 15.451 l4virtio\_input\_absinfo\_t Struct Reference

Information about the absolute axis in the underlying evdev implementation.

```
#include <virtio_input.h>
```

Collaboration diagram for l4virtio\_input\_absinfo\_t:



### 15.451.1 Detailed Description

Information about the absolute axis in the underlying evdev implementation.

Definition at line [33](#) of file [virtio\\_input.h](#).

The documentation for this struct was generated from the following file:


- [l4/l4virtio/virtio\\_input.h](#)

## 15.452 l4virtio\_input\_config\_t Struct Reference

Device configuration for input devices.

```
#include <virtio_input.h>
```

Collaboration diagram for l4virtio\_input\_config\_t:



### 15.452.1 Detailed Description

Device configuration for input devices.

Definition at line 56 of file [virtio\\_input.h](#).

The documentation for this struct was generated from the following file:


- l4/l4virtio/virtio\_input.h

## 15.453 l4virtio\_input\_devids\_t Struct Reference

Device ID information for the device.

```
#include <virtio_input.h>
```

Collaboration diagram for l4virtio\_input\_devids\_t:



### 15.453.1 Detailed Description

Device ID information for the device.

Definition at line 45 of file [virtio\\_input.h](#).

The documentation for this struct was generated from the following file:


- l4/l4virtio/virtio\_input.h

## 15.454 l4virtio\_input\_event\_t Struct Reference

Single event in event or status queue.

```
#include <virtio_input.h>
```

Collaboration diagram for l4virtio\_input\_event\_t:



### 15.454.1 Detailed Description

Single event in event or status queue.

Definition at line 74 of file [virtio\\_input.h](#).

The documentation for this struct was generated from the following file:


- l4/l4virtio/virtio\_input.h

## 15.455 l4virtio\_net\_config\_t Struct Reference

Device configuration for network devices.

```
#include <virtio_net.h>
```

Collaboration diagram for l4virtio\_net\_config\_t:



### 15.455.1 Detailed Description

Device configuration for network devices.

Definition at line 34 of file [virtio\\_net.h](#).

The documentation for this struct was generated from the following file:


- l4/l4virtio/virtio\_net.h

## 15.456 l4virtio\_net\_header\_t Struct Reference

Header structure of a request for a network device.

```
#include <virtio_net.h>
```

Collaboration diagram for l4virtio\_net\_header\_t:



### 15.456.1 Detailed Description

Header structure of a request for a network device.

Definition at line 20 of file [virtio\\_net.h](#).

The documentation for this struct was generated from the following file:

- l4/l4virtio/virtio\_net.h


## 15.457 L4virtio\_port Class Reference

A Port on the Virtio Net Switch.


```
#include <port_l4virtio.h>
```



Inheritance diagram for L4virtio\_port:



Collaboration diagram for L4virtio\_port:



## Public Member Functions

- **L4virtio\_port** (unsigned vq\_max, unsigned num\_ds, char const \*name, [l4\\_uint8\\_t](#) const \*mac)  
*Create a Virtio net port object.*
- bool **tx\_work\_pending** () const  
*Check whether there is any work pending on the transmission queue.*
- std::optional< [Virtio\\_net\\_request](#) > **get\_tx\_request** ()

*Get one request from the transmission queue.*

- void **drop\_requests** ()

*Drop all requests pending in the transmission queue.*

## Public Member Functions inherited from Virtio\_net

- void **reset** () override  
*reset callback, called for doing a device reset*
- int **reconfig\_queue** (unsigned index) override  
*callback for client queue-config request*
- bool **check\_features** () override  
*callback for checking the subset of accepted features*
- bool **check\_queues** () override  
*Check whether both virtqueues are ready.*
- void **register\_single\_driver\_irq** () override  
*Save the \_kick\_guest\_irq that the client sent via device\_notification\_irq().*
- void **trigger\_driver\_config\_irq** () override  
*callback for triggering configuration change notification IRQ*
- void **notify\_queue** (L4virtio::Svr::Virtqueue \*queue)  
*Trigger the \_kick\_guest\_irq IRQ.*
- Virtqueue \* **tx\_q** ()  
*Getter for the transmission queue.*
- Virtqueue \* **rx\_q** ()  
*Getter for the receive queue.*
- Virtqueue const \* **tx\_q** () const  
*Getter for the transmission queue.*
- Virtqueue const \* **rx\_q** () const  
*Getter for the receive queue.*

## Public Member Functions inherited from L4virtio::Svr::Device\_t< No\_custom\_data >

- virtual void **cfg\_changed** (unsigned)  
*callback for client device configuration changes*
- virtual L4::Cap< L4::Irq > **device\_notify\_irq** () const  
*callback to gather the device notification IRQ (old-style)*
- virtual void **register\_driver\_irq** (unsigned idx)  
*Callback for registering an notification IRQ (multi IRQ).*
- virtual L4::Cap< L4::Irq > **device\_notify\_irq** (unsigned idx)  
*Callback to gather the device notification IRQ (multi IRQ).*
- virtual unsigned **num\_events\_supported** () const  
*Return the highest notification index supported.*
- **Device\_t** (Dev\_config \*dev\_config)  
*Make a device for the given config.*
- Mem\_list const \* **mem\_info** () const  
*Get the memory region list used for this device.*
- void **reset\_queue\_config** (unsigned idx, unsigned num\_max, bool inc\_generation=false, unsigned device\_notify\_index=0)  
*Trigger reset for the configuration space for queue idx.*
- void **init\_mem\_info** (unsigned num)

- Initialize the memory region list to the given maximum.*
- void `device_error ()`  
*Transition device into `DEVICE_NEEDS_RESET` state.*
- bool `setup_queue (Virtqueue *q, unsigned qn, unsigned num_max)`  
*Enable/disable the specified queue.*
- bool `handle_mem_cmd_write ()`  
*Check for a value in the `cmd` register and handle a write.*
- void `enable_trusted_ds_validation ()`  
*Enable trusted dataspace validation.*
- void `add_trusted_dataspaces (std::shared_ptr< Ds_vector const > ds)`  
*Provide a list of trusted dataspace that can be used for validation.*

## Public Member Functions inherited from `L4::Epiface_t0< L4virtio::Device, L4::Epiface >`

- `Type_info::Demand get_buffer_demand () const`  
*Get the server-side buffer demand based in `IFACE`.*
- `Cap< L4virtio::Device > obj_cap () const`  
*Get the (typed) capability to this object.*

## Public Member Functions inherited from `L4::Epiface`

- `Epiface ()`  
*Make a server object.*
- virtual `~Epiface ()=0`  
*Destroy the object.*
- Stored\_cap `obj_cap () const`  
*Get the capability to the kernel object belonging to this object.*
- `Server_iface * server_iface () const`  
*Get pointer to server interface at which the object is currently registered.*
- int `set_server (Server_iface *srv, Cap< void > cap, bool managed=false)`  
*Set server registration info for the object.*
- void `set_obj_cap (Cap< void > const &cap)`  
*Deprecated server registration function.*

## Additional Inherited Members

## Public Types inherited from `L4::Epiface_t0< L4virtio::Device, L4::Epiface >`

- typedef `L4virtio::Device Interface`  
*Data type of the IPC interface definition.*

## Public Types inherited from `L4::Epiface`

- typedef `lpc_svr::Server_iface Server_iface`  
*Type for abstract server interface.*
- typedef `lpc_svr::Server_iface::Demand Demand`  
*Type for server-side receive buffer demand.*

## Protected Attributes inherited from [L4virtio::Svr::Device\\_t< No\\_custom\\_data >](#)

- `Mem_list_mem_info`  
*Memory region list.*

### 15.457.1 Detailed Description

A Port on the Virtio Net Switch.

A Port object gets created by `Virtio_factory::op_create()`. This function actually only instantiates objects of the types `Switch_port` and `Monitor_port`. The created Port registers itself at the switch's server. Usually, the IPC call for port creation comes from ned. To finalize the setup, the client has to initialize the port during the virtio initialization phase. To do this, the client registers a dataspace for queues and buffers and provides an IRQ to notify the client on incoming network requests.

Definition at line 36 of file [port\\_l4virtio.h](#).

### 15.457.2 Member Function Documentation

#### 15.457.2.1 drop\_requests()

```
void L4virtio_port::drop_requests () [inline]
```


Drop all requests pending in the transmission queue.

This is used for monitor ports, which are not allowed to send packets.

Definition at line 103 of file [port\\_l4virtio.h](#).

References [Virtio\\_net\\_request::drop\\_requests\(\)](#), and [Virtio\\_net::tx\\_q\(\)](#).

Here is the call graph for this function:



The documentation for this class was generated from the following file:


- `pkg/virtio-net-switch/server/switch/port_l4virtio.h`

## 15.458 Mac\_addr Class Reference

A wrapper class around the value of a MAC address.

```
#include <mac_addr.h>
```

Collaboration diagram for Mac\_addr:



### Public Member Functions

- bool **is\_broadcast** () const  
*Check if MAC address is a broadcast or multicast address.*
- bool **is\_unknown** () const  
*Check if the MAC address is not yet known.*

### 15.458.1 Detailed Description

A wrapper class around the value of a MAC address.

Definition at line 19 of file [mac\\_addr.h](#).

The documentation for this class was generated from the following file:


- pkg/virtio-net-switch/server/switch/mac\_addr.h

## 15.459 Mac\_table< Size > Class Template Reference

[Mac\\_table](#) manages a 1:n association between ports and MAC addresses.

```
#include <mac_table.h>
```

Collaboration diagram for Mac\_table< Size >:



### Public Member Functions

- Port\_iface \* [lookup](#) (Mac\_addr dst, l4\_uint16\_t vlan\_id) const  
*Find the destination port for a MAC address and VLAN id.*
- void [learn](#) (Mac\_addr src, Port\_iface \*port, l4\_uint16\_t vlan\_id)  
*Learn a MAC address (add it to the MAC table).*
- void [flush](#) (Port\_iface \*port)  
*Flush all associations with a given port.*

### 15.459.1 Detailed Description

```
template<std::size_t Size = 1024U>
class Mac_table< Size >
```

[Mac\\_table](#) manages a 1:n association between ports and MAC addresses.

There are different types of devices which might be attached to a port. For a normal device the switch sees exactly one MAC address per port - the MAC address of the device attached to it. But there might be other devices like software bridges attached to the port sending packets with different MAC addresses to the port. Therefore the switch has to manage a 1:n association between ports and MAC addresses. The MAC table manages this association.

When a packet comes in we need to find the destination port for the packet and therefore perform a lookup based on the MAC address.

To prevent unbounded growth of the lookup table, the number of entries is limited. Replacement is done on a round-robin basis. If the capacity was reached, the oldest entry is evicted.

Definition at line 40 of file [mac\\_table.h](#).

## 15.459.2 Member Function Documentation

### 15.459.2.1 flush()

```
template<std::size_t Size = 1024U>
void Mac_table< Size >::flush (
    Port_iface * port) [inline]
```

Flush all associations with a given port.

#### Parameters

<i>port</i>	Pointer to port that is to be flushed
-------------	---------------------------------------

This function removes all references to a given port from the MAC table. Since we manage a 1:n association between ports and MAC addresses there might be more than one entry for a given port and we have to iterate over the whole array to delete every reference to the port.

Definition at line 129 of file [mac\\_table.h](#).

### 15.459.2.2 learn()

```
template<std::size_t Size = 1024U>
void Mac_table< Size >::learn (
    Mac_addr src,
    Port_iface * port,
    14_uint16_t vlan_id) [inline]
```

Learn a MAC address (add it to the MAC table).

#### Parameters

<i>src</i>	MAC address
<i>port</i>	Pointer to the port object that can be used to reach MAC address src
<i>vlan_id</i>	VLAN id of the packet destination.

Will evict the oldest learned address from the table if the maximum capacity was reached and if the MAC address was not known yet. The source port of the table entry is always updated to cope with clients that move between ports.

Definition at line 78 of file [mac\\_table.h](#).

References [L4\\_UNLIKELY](#), and [lookup\(\)](#).

Here is the call graph for this function:





### 15.459.2.3 lookup()

```
template<std::size_t Size = 1024U>
Port_iface * Mac_table< Size >::lookup (
    Mac_addr dst,
    14_uint16_t vlan_id) const [inline]
```

Find the destination port for a MAC address and VLAN id.

#### Parameters

<i>dst</i>	MAC address
<i>vlan↔ _id</i>	VLAN id

#### Return values

<i>nullptr</i>	The MAC address is not known (yet)
<i>other</i>	Pointer to the destination port

Definition at line 58 of file [mac\\_table.h](#).

Referenced by [learn\(\)](#).

Here is the caller graph for this function:



The documentation for this class was generated from the following file:


- [pkg/virtio-net-switch/server/switch/mac\\_table.h](#)

## 15.460 Net\_transfer Class Reference

A network request to only a single destination.

```
#include <request.h>
```

Collaboration diagram for Net\_transfer:



### Public Member Functions

- void const \* **req\_id** () const  
*Identifier for the underlying Net\_request, used for logging purposes.*
- virtual void **copy\_header** (Virtio\_net::Hdr \*dst\_header) const =0  
*Populate the virtio-net header for the destination.*
- **Buffer** & **cur\_buf** ()  
*Buffer containing (a part of) the packet data.*
- virtual bool **done** ()=0  
*Check whether the transfer has been completed, i.e.*

## 15.460.1 Detailed Description

A network request to only a single destination.

A `Net_request` can have multiple destinations (being a broadcast request, for example). That is why it is processed by multiple `Net_transfers`, each representing the delivery to a single destination port.

`Port_iface::handle_request` uses the `Net_transfer` to move one packet to the destination of the request.

Definition at line 33 of file [request.h](#).

## 15.460.2 Member Function Documentation

### 15.460.2.1 `cur_buf()`

```
Buffer & Net_transfer::cur_buf () [inline]
```

`Buffer` containing (a part of) the packet data.

Once emptied, a call to `done()` might replenish the buffer, in case the net request consisted of multiple chained buffers.

Definition at line 54 of file [request.h](#).

### 15.460.2.2 `done()`

```
virtual bool Net_transfer::done () [pure virtual]
```

Check whether the transfer has been completed, i.e.

the entire packet data has been copied.

#### Return values

<i>false</i>	There is remaining packet data that needs to be copied.
<i>true</i>	The entire packet data has been copied.

#### Exceptions

<a href="#">L4virtio::Svr::Bad_descriptor</a>	Exception raised in SRC port queue.
---	-------------------------------------

The documentation for this class was generated from the following file:


- `pkg/virtio-net-switch/server/switch/request.h`

## 15.461 Rm Class Reference


Region map.

```
#include <l4/re/rm>
```

Inheritance diagram for Rm:



Collaboration diagram for Rm:



## Data Structures

- struct [F](#)  
*Rm flags definitions.*
- class [Unique\\_region](#)  
*Unique region.*
- struct [Region](#)

*A region is a range of virtual addresses which is backed by content.*

- struct [Area](#)

*An area is a range of virtual addresses which is reserved, see [L4Re::Rm::reserve\\_area\(\)](#).*

## Public Types

- enum [Detach\\_result](#) { [Detached\\_ds](#) = 0 , [Kept\\_ds](#) = 1 , [Split\\_ds](#) = 2 , [Detach\\_result\\_mask](#) = 3 , [Detach\\_again](#) = 4 }
- Result values for detach operation.*
- enum [Region\\_flag\\_shifts](#) { [Caching\\_shift](#) = Dataspace::F::Caching\_shift }
- Region flag shifts.*
- enum [Detach\\_flags](#) { [Detach\\_exact](#) = 1 , [Detach\\_overlap](#) = 2 , [Detach\\_keep](#) = 4 }
- Flags for detach operation.*

## Public Member Functions

- [l4\\_ret\\_t reserve\\_area](#) ([l4\\_addr\\_t](#) \*start, unsigned long size, Flags flags=[Flags](#)(0), unsigned char align=[L4\\_PAGESHIFT](#)) const noexcept
- Reserve the given area in the region map.*
- template<typename T>  
[l4\\_ret\\_t reserve\\_area](#) (T \*\*start, unsigned long size, Flags flags=[Flags](#)(0), unsigned char align=[L4\\_PAGESHIFT](#)) const noexcept
- Reserve the given area in the region map.*
- [l4\\_ret\\_t free\\_area](#) ([l4\\_addr\\_t](#) addr)
- Free an area from the region map.*
- [l4\\_ret\\_t attach](#) ([l4\\_addr\\_t](#) \*start, unsigned long size, Flags flags, [L4::lpc::Cap](#)< Dataspace > mem, Offset offs=0, unsigned char align=[L4\\_PAGESHIFT](#), [L4::Cap](#)< [L4::Task](#) > const task=[L4::Cap](#)< [L4::Task](#) >::Invalid, char const \*name=nullptr, Offset backing\_offset=0) const noexcept
- Attach a data space to a region.*
- template<typename T>  
[l4\\_ret\\_t attach](#) (T \*\*start, unsigned long size, Flags flags, [L4::lpc::Cap](#)< Dataspace > mem, Offset offs=0, unsigned char align=[L4\\_PAGESHIFT](#), [L4::Cap](#)< [L4::Task](#) > const task=[L4::Cap](#)< [L4::Task](#) >::Invalid, char const \*name=nullptr, Offset backing\_offset=0) const noexcept
- Attach a data space to a region.*
- [l4\\_ret\\_t detach](#) ([l4\\_addr\\_t](#) addr, [L4::Cap](#)< Dataspace > \*mem, [L4::Cap](#)< [L4::Task](#) > const &task=[This\\_task](#)) const noexcept
- Detach and unmap a region from the address space.*
- [l4\\_ret\\_t detach](#) (void \*addr, [L4::Cap](#)< Dataspace > \*mem, [L4::Cap](#)< [L4::Task](#) > const &task=[This\\_task](#)) const noexcept
- Detach and unmap a region from the address space.*
- [l4\\_ret\\_t detach](#) ([l4\\_addr\\_t](#) start, unsigned long size, [L4::Cap](#)< Dataspace > \*mem, [L4::Cap](#)< [L4::Task](#) > const &task) const noexcept
- Detach and unmap all parts of the regions within the specified interval.*
- [l4\\_ret\\_t find](#) ([l4\\_addr\\_t](#) \*addr, unsigned long \*size, Offset \*offset, [L4Re::Rm::Flags](#) \*flags, [L4::Cap](#)< Dataspace > \*m) noexcept
- Find a region given an address and size.*
- [l4\\_ret\\_t get\\_regions](#) ([l4\\_addr\\_t](#) start, [L4::lpc::Ret\\_array](#)< [Region](#) > regions)
- Return the list of regions whose starting addresses are higher or equal to *start* in the address space managed by this region map.*
- long [get\\_areas](#) ([l4\\_addr\\_t](#) start, [L4::lpc::Ret\\_array](#)< [Area](#) > areas)
- Return the list of areas whose starting addresses are higher or equal to *start* in the address space managed by this region map.*
- [l4\\_ret\\_t get\\_info](#) ([l4\\_addr\\_t](#) addr, [L4::lpc::String](#)< char > &name, Offset &backing\_offset)
- Return auxiliary information of a region.*

## Public Member Functions inherited from [L4::Pager](#)

- [l4\\_msgtag\\_t](#) [page\\_fault](#) ([l4\\_umword\\_t](#) pfa, [l4\\_umword\\_t](#) pc, [L4::lpc::Rcv\\_fpage](#) rwin, [L4::lpc::Opt<L4::lpc::Snd\\_fpage & >](#) fp)

*Page-fault protocol message.*

## Public Member Functions inherited from [L4::io\\_pager](#)

- [l4\\_msgtag\\_t](#) [io\\_page\\_fault](#) ([l4\\_fpage\\_t](#) io\_pfa, [l4\\_umword\\_t](#) pc, [L4::lpc::Rcv\\_fpage](#) rwin, [L4::lpc::Opt<L4::lpc::Snd\\_fpage & >](#) fp)

*IO page fault protocol message.*

## Additional Inherited Members

### Protected Types inherited from

[L4::Kobject\\_t< Rm, L4::Pager, L4RE\\_PROTO\\_RM, L4::Type\\_info::Demand\\_t< 1 > >](#)

- typedef [Rm](#) **Class**  
*The target interface type (inheriting from [Kobject\\_t](#)).*
- typedef Typeid::Iface< PROTO, [Rm](#) > **\_\_Iface**  
*The interface description for the derived class.*
- typedef Typeid::Merge\_list< Typeid::Iface\_list< **\_\_Iface** >, typename [L4::Pager::\\_\\_Iface\\_list](#) > **\_\_Iface\_list**  
*The list of all RPC interfaces provided directly or through inheritance.*

### Protected Types inherited from

[L4::Kobject\\_t< Pager, io\\_pager, L4\\_PROTO\\_PAGE\\_FAULT >](#)

- typedef [Pager](#) **Class**  
*The target interface type (inheriting from [Kobject\\_t](#)).*
- typedef Typeid::Iface< PROTO, [Pager](#) > **\_\_Iface**  
*The interface description for the derived class.*
- typedef Typeid::Merge\_list< Typeid::Iface\_list< **\_\_Iface** >, typename [io\\_pager::\\_\\_Iface\\_list](#) > **\_\_Iface\_list**  
*The list of all RPC interfaces provided directly or through inheritance.*

### Protected Member Functions inherited from

[L4::Kobject\\_t< Rm, L4::Pager, L4RE\\_PROTO\\_RM, L4::Type\\_info::Demand\\_t< 1 > >](#)

- [L4::Cap< Class >](#) **c** () const noexcept  
*Get the capability to ourselves.*

### Protected Member Functions inherited from

[L4::Kobject\\_t< Pager, io\\_pager, L4\\_PROTO\\_PAGE\\_FAULT >](#)

- [L4::Cap< Class >](#) **c** () const noexcept  
*Get the capability to ourselves.*

**Static Protected Member Functions inherited from****[L4::Kobject\\_t< Rm, L4::Pager, L4RE\\_PROTO\\_RM, L4::Type\\_info::Demand\\_t< 1 > >](#)**

- static void **\_\_check\_protocols\_\_** () noexcept  
*Helper to check for protocol conflicts.*

**Static Protected Member Functions inherited from****[L4::Kobject\\_t< Pager, lo\\_pager, L4\\_PROTO\\_PAGE\\_FAULT >](#)**

- static void **\_\_check\_protocols\_\_** () noexcept  
*Helper to check for protocol conflicts.*

**15.461.1 Detailed Description**

[Region](#) map.

See also

[Region map API](#) .

Definition at line [81](#) of file [rm](#).

**15.461.2 Member Enumeration Documentation****15.461.2.1 Detach\_flags**

enum [L4Re::Rm::Detach\\_flags](#)

Flags for detach operation.

**Enumerator**

Detach_exact	Do an unmap of the exact region given.
Detach_overlap	Do an unmap of all overlapping regions.
Detach_keep	Do not free the detached data space, ignore the <a href="#">F::Detach_free</a> .

Definition at line [215](#) of file [rm](#).



### 15.461.2.2 Detach\_result

enum `L4Re::Rm::Detach_result`

Result values for detach operation.

#### Enumerator

Detached_ds	Detached data sapce.
Kept_ds	Kept data space.
Split_ds	Splitted data space, and done.
Detach_again	Detached data space, more to do.

Definition at line 89 of file `rm`.

### 15.461.2.3 Region\_flag\_shifts

enum `L4Re::Rm::Region_flag_shifts`

`Region` flag shifts.

#### Enumerator

Caching_shift	Start of <code>Rm</code> cache bits.
---------------	--------------------------------------

Definition at line 100 of file `rm`.

## 15.461.3 Member Function Documentation

### 15.461.3.1 attach() [1/2]

```

l4_ret_t L4Re::Rm::attach (
    l4_addr_t * start,
    unsigned long size,
    Rm::Flags flags,
    L4::Ipc::Cap< Dataspace > mem,
    Rm::Offset offs = 0,
    unsigned char align = L4_PAGESHIFT,
    L4::Cap< L4::Task > const task = L4::Cap<L4::Task>::Invalid,
    char const * name = nullptr,
    Rm::Offset backing_offset = 0) const [noexcept]

```

Attach a data space to a region.

#### Parameters

<i>in, out</i>	<i>start</i>	Virtual start address where the region manager shall attach the data space. Will be rounded down to the nearest start of a page. If <a href="#">L4Re::Rm::F::Search_addr</a> is given this value is used as the start address to search for a free virtual memory region and the resulting address is returned here. If <a href="#">L4Re::Rm::F::In_area</a> is given the value is used as a selector for the area (see <a href="#">L4Re::Rm::reserve_area</a> ) to attach the data space to.
	<i>size</i>	Size of the data space to attach (in bytes). Will be rounded up to the nearest multiple of the page size.
	<i>flags</i>	The flags control how and with which rights the dataspace is attached to the region. See <a href="#">L4Re::Rm::F::Attach_flags</a> and <a href="#">L4Re::Rm::F::Region_flags</a> . The caller must specify the desired rights of the attached region explicitly. The default set of rights is empty. If the <a href="#">F::Eager_map</a> flag is set this function may also return <a href="#">L4Re::Dataspace::map</a> error codes if the mapping fails.
	<i>mem</i>	Data space.
	<i>offs</i>	Offset into the data space to use.
	<i>align</i>	Alignment of the virtual region, log2-size, default: a page ( <a href="#">L4_PAGESHIFT</a> ). This is only meaningful if the <a href="#">L4Re::Rm::F::Search_addr</a> flag is used.
	<i>task</i>	Optional destination task of mapping if <a href="#">F::Eager_map</a> flag was passed. If invalid, the mapping is established in the current task. This parameter is only useful if the region manager is for a foreign task.
	<i>name</i>	Optional name of the region.
	<i>backing_offset</i>	Optional value describing an offset into the backing store of this region.

### Return values

0	Success
-L4_ENOENT	No area could be found (see <a href="#">L4Re::Rm::F::In_area</a> )
-L4_EPERM	Operation not allowed.
-L4_EINVAL	
-L4_EADDRNOTAVAIL	The given address is not available.
<0	IPC errors

Makes the whole or parts of a data space visible in the virtual memory of the corresponding task. The corresponding region in the virtual address space is backed with the contents of the dataspace.

### Note

When searching for a free place in the virtual address space, the space between *start* and the end of the virtual address space is searched.

There is no region object created, instead the region is defined by a virtual address within this range (see [L4Re::Rm::find](#)).

Definition at line 35 of file [rm\\_impl.h](#).

### 15.461.3.2 attach() [2/2]

```
template<typename T>
l4_ret_t L4Re::Rm::attach (
```

```

T ** start,
unsigned long size,
Flags flags,
L4::Ipc::Cap< Dataspace > mem,
Offset offs = 0,
unsigned char align = L4_PAGESHIFT,
L4::Cap< L4::Task > const task = L4::Cap<L4::Task>::Invalid,
char const * name = nullptr,
Offset backing_offset = 0) const [inline], [noexcept]

```

Attach a data space to a region.

### Parameters

in, out	<i>start</i>	Virtual start address where the region manager shall attach the data space. Will be rounded down to the nearest start of a page. If <a href="#">L4Re::Rm::F::Search_addr</a> is given this value is used as the start address to search for a free virtual memory region and the resulting address is returned here. If <a href="#">L4Re::Rm::F::In_area</a> is given the value is used as a selector for the area (see <a href="#">L4Re::Rm::reserve_area</a> ) to attach the data space to.
	<i>size</i>	Size of the data space to attach (in bytes). Will be rounded up to the nearest multiple of the page size.
	<i>flags</i>	The flags control how and with which rights the dataspace is attached to the region. See <a href="#">L4Re::Rm::F::Attach_flags</a> and <a href="#">L4Re::Rm::F::Region_flags</a> . The caller must specify the desired rights of the attached region explicitly. The default set of rights is empty. If the <a href="#">F::Eager_map</a> flag is set this function may also return <a href="#">L4Re::Dataspace::map</a> error codes if the mapping fails.
	<i>mem</i>	Data space.
	<i>offs</i>	Offset into the data space to use.
	<i>align</i>	Alignment of the virtual region, log2-size, default: a page ( <a href="#">L4_PAGESHIFT</a> ). This is only meaningful if the <a href="#">L4Re::Rm::F::Search_addr</a> flag is used.
	<i>task</i>	Optional destination task of mapping if <a href="#">F::Eager_map</a> flag was passed. If invalid, the mapping is established in the current task. This parameter is only useful if the region manager is for a foreign task.
	<i>name</i>	Optional name of the region.
	<i>backing_offset</i>	Optional value describing an offset into the backing store of this region.

### Return values

0	Success
-L4_ENOENT	No area could be found (see <a href="#">L4Re::Rm::F::In_area</a> )
-L4_EPERM	Operation not allowed.
-L4_EINVAL	
-L4_EADDRNOTAVAIL	The given address is not available.
<0	IPC errors

Makes the whole or parts of a data space visible in the virtual memory of the corresponding task. The corresponding region in the virtual address space is backed with the contents of the dataspace.

**Note**

When searching for a free place in the virtual address space, the space between *start* and the end of the virtual address space is searched.

There is no region object created, instead the region is defined by a virtual address within this range (see [L4Re::Rm::find](#)).

Definition at line 408 of file [rm](#).

**15.461.3.3 detach() [1/3]**

```
l4_ret_t L4Re::Rm::detach (
    l4_addr_t addr,
    L4::Cap< Dataspace > * mem,
    L4::Cap< L4::Task > const & task = This_task) const [inline], [noexcept]
```

Detach and unmap a region from the address space.

**Parameters**

	<i>addr</i>	Virtual address of region, any address within the region is valid.
out	<i>mem</i>	Dataspace that is affected. Give 0 if not interested.
	<i>task</i>	This argument specifies the task where the pages are unmapped. Provide <a href="#">L4::Cap&lt;L4::Task&gt;::Invalid</a> for none. The default is the current task.

**Return values**

<a href="#">L4Re::Rm::Detach_result</a>	On success.
<i>-L4_ENOENT</i>	No region found.
<i>&lt;0</i>	IPC errors

Frees a region in the virtual address space given by *addr* (address type). The corresponding part of the address space is now available again.

Definition at line 762 of file [rm](#).

**15.461.3.4 detach() [2/3]**

```
l4_ret_t L4Re::Rm::detach (
    l4_addr_t start,
    unsigned long size,
    L4::Cap< Dataspace > * mem,
    L4::Cap< L4::Task > const & task) const [inline], [noexcept]
```

Detach and unmap all parts of the regions within the specified interval.

**Parameters**

	<i>start</i>	Start of area to detach, must be within region.
	<i>size</i>	Size of of area to detach (in bytes).
out	<i>mem</i>	Dataspace that is affected. Give 0 if not interested.
	<i>task</i>	This argument specifies the task where the pages are unmapped. Provide <a href="#">L4::Cap&lt;L4::Task&gt;::Invalid</a> for none. The default is the current task.

### Return values

<a href="#">L4Re::Rm::Detach_result</a>	On success.
<a href="#">-L4_ENOENT</a>	No region found.
<a href="#">&lt;0</a>	IPC errors

Frees all regions within the interval given by start and size. If a region overlaps the start or the end of the interval this region is only detached partly. If the interval is within one region the original region is split up into two separate regions.

Definition at line [775](#) of file [rm](#).

### 15.461.3.5 detach() [3/3]

```
l4_ret_t L4Re::Rm::detach (
    void * addr,
    L4::Cap< Dataspace > * mem,
    L4::Cap< L4::Task > const & task = This_task) const [inline], [noexcept]
```

Detach and unmap a region from the address space.

### Parameters

	<i>addr</i>	Virtual address of region, any address within the region is valid.
out	<i>mem</i>	Dataspace that is affected. Give 0 if not interested.
	<i>task</i>	This argument specifies the task where the pages are unmapped. Provide <a href="#">L4::Cap&lt;L4::Task&gt;::Invalid</a> for none. The default is the current task.

### Return values

<a href="#">L4Re::Rm::Detach_result</a>	On success.
<a href="#">-L4_ENOENT</a>	No region found.
<a href="#">&lt;0</a>	IPC errors

Frees a region in the virtual address space given by addr (address type). The corresponding part of the address space is now available again.

Definition at line [767](#) of file [rm](#).



**15.461.3.7 free\_area()**

```
l4_ret_t L4Re::Rm::free_area (
    l4_addr_t addr)
```

Free an area from the region map.

**Parameters**

<i>addr</i>	An address within the area to free.
-------------	-------------------------------------

**Return values**

0	Success
-L4_ENOENT	No area found.
<0	IPC errors

**Note**

The data spaces that are attached to that area are not detached by this operation.

**See also**

[reserve\\_area\(\)](#) for more information about areas.

**15.461.3.8 get\_areas()**

```
long L4Re::Rm::get_areas (
    l4_addr_t start,
    L4::Ipc::Ret_array< Area > areas)
```

Return the list of areas whose starting addresses are higher or equal to *start* in the address space managed by this region map.

**Parameters**

	<i>start</i>	Virtual address from where to start searching.
out	<i>areas</i>	List of areas found in this region map.

**Return values**

>=0	Number of returned areas in the <i>areas</i> array.
<0	IPC errors

**Note**

The returned list of areas might not be complete and the caller shall use the function repeatedly with a start address one larger than the end address of the last area from the previous call.

**15.461.3.9 get\_info()**

```
l4_ret_t L4Re::Rm::get_info (
    l4_addr_t addr,
    L4::Ipc::String< char > & name,
    Offset & backing_offset)
```

Return auxiliary information of a region.

This is a debugging feature and might not be available.

**Parameters**

	<i>addr</i>	Virtual address of the region.
out	<i>name</i>	Name of the region.
out	<i>backing_offset</i>	Backing offset information.

**Return values**

<i>0</i>	Success
<i>-L4_ENOENT</i>	<a href="#">Region</a> not found.
<i>-L4_ENOSYS</i>	Function not available.
<i>&lt;0</i>	IPC errors

**15.461.3.10 get\_regions()**

```
l4_ret_t L4Re::Rm::get_regions (
    l4_addr_t start,
    L4::Ipc::Ret_array< Region > regions)
```

Return the list of regions whose starting addresses are higher or equal to *start* in the address space managed by this region map.

**Parameters**

	<i>start</i>	Virtual address from where to start searching.
out	<i>regions</i>	List of regions found in this region map.

**Return values**

<i>&gt;=0</i>	Number of returned regions in the <i>regions</i> array.
<i>&lt;0</i>	IPC errors

**Note**

The returned list of regions might not be complete and the caller shall use the function repeatedly with a start address one larger than the end address of the last region from the previous call.



**15.461.3.11 reserve\_area()** [1/2]

```
l4_ret_t L4Re::Rm::reserve_area (
    l4_addr_t * start,
    unsigned long size,
    Flags flags = Flags(0),
    unsigned char align = L4_PAGESHIFT) const [inline], [noexcept]
```

Reserve the given area in the region map.

**Parameters**

<i>in, out</i>	<i>start</i>	The virtual start address of the area to reserve. Returns the start address of the area.
	<i>size</i>	The size of the area to reserve (in bytes).
	<i>flags</i>	Flags for the reserved area (see <a href="#">L4Re::Rm::F::Region_flags</a> and <a href="#">L4Re::Rm::F::Attach_flags</a> ).
	<i>align</i>	Alignment of area if searched as bits (log2 value).

**Return values**

0	Success
-L4_EADDRNOTAVAIL	The given area cannot be reserved.
<0	IPC errors

This function reserves an area within the virtual address space managed by the region map. There are two kinds of areas available:

- Reserved areas (*flags* = [L4Re::Rm::F::Reserved](#)), where no data spaces can be attached
- Special purpose areas (*flags* = 0), where data spaces can be attached to the area via the [L4Re::Rm::F::In\\_area](#) flag and a start address within the area itself.

**Note**

When searching for a free place in the virtual address space (with *flags* = [L4Re::Rm::F::Search\\_addr](#)), the space between *start* and the end of the virtual address space is searched.

Definition at line 276 of file [rm](#).

**15.461.3.12 reserve\_area()** [2/2]

```
template<typename T>
l4_ret_t L4Re::Rm::reserve_area (
    T ** start,
    unsigned long size,
    Flags flags = Flags(0),
    unsigned char align = L4_PAGESHIFT) const [inline], [noexcept]
```

Reserve the given area in the region map.

**Parameters**

<i>in, out</i>	<i>start</i>	The virtual start address of the area to reserve. Returns the start address of the area.
	<i>size</i>	The size of the area to reserve (in bytes).
	<i>flags</i>	Flags for the reserved area (see <a href="#">F::Region_flags</a> and <a href="#">F::Attach_flags</a> ).
	<i>align</i>	Alignment of area if searched as bits (log2 value).

**Return values**

<i>0</i>	Success
<i>-L4_EADDRNOTAVAIL</i>	The given area cannot be reserved.
<i>&lt;0</i>	IPC errors

For more information, please refer to the analogous function

**See also**

[L4Re::Rm::reserve\\_area](#).

Definition at line [304](#) of file [rm](#).

The documentation for this class was generated from the following files:


- [l4/re/rm](#)
- [l4/re/impl/rm\\_impl.h](#)

**15.462 Rm::Area Struct Reference**

An area is a range of virtual addresses which is reserved, see [L4Re::Rm::reserve\\_area\(\)](#).

```
#include <rm>
```

Collaboration diagram for Rm::Area:



### 15.462.1 Detailed Description

An area is a range of virtual addresses which is reserved, see [L4Re::Rm::reserve\\_area\(\)](#).

See also

[Region map API](#)

Definition at line 698 of file [rm](#).

The documentation for this struct was generated from the following file:


- [l4/re/rm](#)

## 15.463 Rm::F Struct Reference

[Rm](#) flags definitions.

```
#include <rm>
```

Collaboration diagram for Rm::F:



### Public Types

- enum [Attach\\_flags](#) : `l4_uint32_t` {  
[Search\\_addr](#) = 0x20000 , [In\\_area](#) = 0x40000 , [Eager\\_map](#) = 0x80000 , [No\\_eager\\_map](#) = 0x100000 ,  
[Attach\\_mask](#) = 0x1f0000 }  
*Flags for attach operation.*
- enum [Region\\_flags](#) : `l4_uint16_t` {  
[Rights\\_mask](#) = 0x0f , [R](#) = `Dataspace::F::R` , [W](#) = `Dataspace::F::W` , [X](#) = `Dataspace::F::X` ,  
[RW](#) = `Dataspace::F::RW` , [RX](#) = `Dataspace::F::RX` , [RWX](#) = `Dataspace::F::RWX` , [Kernel](#) = 0x100 ,  
[Detach\\_free](#) = 0x200 , [Pager](#) = 0x400 , [Reserved](#) = 0x800 , [Caching\\_mask](#) = `Dataspace::F::Caching_mask` ,  
[Cache\\_normal](#) = `Dataspace::F::Normal` , [Cache\\_buffered](#) = `Dataspace::F::Bufferable` , [Cache\\_uncached](#) =  
`Dataspace::F::Uncacheable` , [Ds\\_map\\_mask](#) = 0xff ,  
[Region\\_flags\\_mask](#) = 0xffff }  
*Region flags (permissions, cacheability, special).*

### 15.463.1 Detailed Description

[Rm](#) flags definitions.

Definition at line 107 of file [rm](#).

### 15.463.2 Member Enumeration Documentation

#### 15.463.2.1 Attach\_flags

```
enum L4Re::Rm::F::Attach_flags : 14_uint32_t
```

Flags for attach operation.

##### Enumerator

Search_addr	Search for a suitable address range.
In_area	Search only in area, or map into area.
Eager_map	Eagerly map the attached data space in.
No_eager_map	Prevent eager mapping of the attached data space.
Attach_mask	Mask of all attach flags.

Definition at line 110 of file [rm](#).

#### 15.463.2.2 Region\_flags

```
enum L4Re::Rm::F::Region_flags : 14_uint16_t
```

[Region](#) flags (permissions, cacheability, special).

##### Enumerator

Rights_mask	<a href="#">Region</a> rights.
R	Readable region.
W	Writable region.
X	Executable region.
RW	Readable and writable region.
RX	Readable and executable region.
RWX	Readable, writable and executable region.
Kernel	Kernel-provided memory (KUMEM).
Detach_free	Free the portion of the data space after detach.
Pager	<a href="#">Region</a> has a pager.
Reserved	<a href="#">Region</a> is reserved (blocked).
Caching_mask	Mask of all <a href="#">Rm</a> cache bits.

Cache_normal	Cache bits for normal cacheable memory. This is the default if no other cache-related flag was specified.
Cache_buffered	Cache bits for buffered (write combining) memory.
Cache_uncached	Cache bits for uncached memory.
Ds_map_mask	Mask for all bits for cache options and rights.
Region_flags_mask	Mask of all region flags.

Definition at line 128 of file [rm](#).

The documentation for this struct was generated from the following file:


- [l4/re/rm](#)

## 15.464 Rm::Region Struct Reference

A region is a range of virtual addresses which is backed by content.

```
#include <rm>
```

Collaboration diagram for Rm::Region:



### 15.464.1 Detailed Description

A region is a range of virtual addresses which is backed by content.

See also

[Region map API](#)

Definition at line 685 of file [rm](#).

The documentation for this struct was generated from the following file:


- [l4/re/rm](#)

## 15.465 Rm::Unique\_region< T > Class Template Reference

Unique region.

```
#include <rm>
```

Inheritance diagram for Rm::Unique\_region< T >:



Collaboration diagram for Rm::Unique\_region< T >:

Rm::Unique_region< T >
<ul style="list-style-type: none"> <li>+ Unique_region()</li> <li>+ Unique_region()</li> <li>+ Unique_region()</li> <li>+ Unique_region()</li> <li>+ operator=()</li> <li>+ ~Unique_region()</li> <li>+ get()</li> <li>+ release()</li> <li>+ reset()</li> <li>+ reset()</li> <li>+ is_valid()</li> <li>+ operator*()</li> <li>+ operator-&gt;()</li> </ul>

## Public Member Functions

- **Unique\_region** () noexcept  
*Construct an invalid [Unique\\_region](#).*
- [Unique\\_region](#) (T addr) noexcept  
*Construct a [Unique\\_region](#) from an address.*
- [Unique\\_region](#) (T addr, [L4::Cap](#)< [Rm](#) > const &rm) noexcept  
*Construct a valid [Unique\\_region](#) from an address and a region manager.*
- [Unique\\_region](#) (Unique\_region &&o) noexcept  
*Move-Construct a [Unique\\_region](#).*
- Unique\_region & [operator=](#) (Unique\_region &&o) noexcept  
*Move-assign a [Unique\\_region](#).*
- [~Unique\\_region](#) () noexcept  
*Destructor.*
- T [get](#) () const noexcept  
*Return the address.*
- T [release](#) () noexcept  
*Return the address and invalidate the [Unique\\_region](#).*
- void [reset](#) (T addr, [L4::Cap](#)< [Rm](#) > const &rm) noexcept  
*Set new address and region manager.*
- void **reset** () noexcept  
*Make the [Unique\\_region](#) invalid.*

- `bool is_valid ()` const noexcept  
*Check if the `Unique_region` is valid.*
- `T operator* ()` const noexcept  
*Dereference the address.*
- `T operator-> ()` const noexcept  
*Member access for the address.*

### 15.465.1 Detailed Description

```
template<typename T>
class Rm::Unique_region< T >
```

Unique region.

Capture a single region with automatic detach on destruction and unique ownership. Stores the start address and the region-mapper capability internally. A unique region is valid precisely if the internal region-mapper capability is valid. The features for unique ownership and automatic detach are only active for valid unique regions.

Definition at line 434 of file `rm`.

### 15.465.2 Constructor & Destructor Documentation

#### 15.465.2.1 Unique\_region() [1/3]

```
template<typename T>
L4Re::Rm::Unique_region< T >::Unique_region (
    T addr) [inline], [explicit], [noexcept]
```

Construct a `Unique_region` from an address.

No region manager is set.

#### Parameters

<code>addr</code>	The new address
-------------------	-----------------

Definition at line 455 of file `rm`.



**15.465.2.2 Unique\_region()** [2/3]

```
template<typename T>
L4Re::Rm::Unique_region< T >::Unique_region (
    T addr,
    L4::Cap< Rm > const & rm) [inline], [noexcept]
```

Construct a valid [Unique\\_region](#) from an address and a region manager.

**Parameters**

<i>addr</i>	The address
<i>rm</i>	The region manager

Definition at line [464](#) of file [rm](#).

**15.465.2.3 Unique\_region()** [3/3]

```
template<typename T>
L4Re::Rm::Unique_region< T >::Unique_region (
    Unique_region< T > && o) [inline], [noexcept]
```

Move-Construct a [Unique\\_region](#).

**Parameters**

<i>o</i>	L-value reference to other region.
----------	------------------------------------

Definition at line [472](#) of file [rm](#).

**15.465.2.4 ~Unique\_region()**

```
template<typename T>
L4Re::Rm::Unique_region< T >::~~Unique_region () [inline], [noexcept]
```

Destructor.

If the region is valid, call [detach](#).

Definition at line [497](#) of file [rm](#).

**15.465.3 Member Function Documentation****15.465.3.1 get()**

```
template<typename T>
T L4Re::Rm::Unique_region< T >::get () const [inline], [noexcept]
```

Return the address.

**Returns**

the address

Definition at line [508](#) of file [rm](#).

### 15.465.3.2 is\_valid()

```
template<typename T>
bool L4Re::Rm::Unique_region< T >::is_valid () const [inline], [noexcept]
```

Check if the `Unique_region` is valid.

#### Returns

true iff the `Unique_region` is valid

Definition at line 548 of file `rm`.

### 15.465.3.3 operator=()

```
template<typename T>
Unique_region & L4Re::Rm::Unique_region< T >::operator= (
    Unique_region< T > && o) [inline], [noexcept]
```

Move-assign a `Unique_region`.

#### Parameters

<i>o</i>	L-value reference to region to assign from
----------	--

Definition at line 480 of file `rm`.

### 15.465.3.4 release()

```
template<typename T>
T L4Re::Rm::Unique_region< T >::release () [inline], [noexcept]
```

Return the address and invalidate the `Unique_region`.

#### Returns

the address

Definition at line 516 of file `rm`.

### 15.465.3.5 reset()

```
template<typename T>
void L4Re::Rm::Unique_region< T >::reset (
    T addr,
    L4::Cap< Rm > const & rm) [inline], [noexcept]
```

Set new address and region manager.

#### Parameters

<i>addr</i>	The new address
<i>rm</i>	The new region manager

Definition at line 528 of file [rm](#).


The documentation for this class was generated from the following file:

- [l4/re/rm](#)


## 15.466 Switch\_factory Class Reference

The IPC interface for creating ports.

Inheritance diagram for Switch\_factory:



Collaboration diagram for Switch\_factory:



### Public Member Functions

- long `op_create` (L4::Factory::Rights, L4::lpc::Cap< void > &res, l4\_umword\_t type, L4::lpc::Varg\_list\_ref va)  
Handle factory protocol.

### Public Member Functions inherited from L4::Epiface\_t0< L4::Factory, L4::Epiface >

- Type\_info::Demand `get_buffer_demand` () const

*Get the server-side buffer demand based in IFACE.*

- `Cap< L4::Factory > obj_cap () const`

*Get the (typed) capability to this object.*

## Public Member Functions inherited from `L4::Epiface`

- `Epiface ()`

*Make a server object.*

- `virtual ~Epiface ()=0`

*Destroy the object.*

- `Stored_cap obj_cap () const`

*Get the capability to the kernel object belonging to this object.*

- `Server_iface * server_iface () const`

*Get pointer to server interface at which the object is currently registered.*

- `int set_server (Server_iface *srv, Cap< void > cap, bool managed=false)`

*Set server registration info for the object.*

- `void set_obj_cap (Cap< void > const &cap)`

*Deprecated server registration function.*

## Additional Inherited Members

## Public Types inherited from `L4::Epiface_t0< L4::Factory, L4::Epiface >`

- `typedef L4::Factory Interface`

*Data type of the IPC interface definition.*

## Public Types inherited from `L4::Epiface`

- `typedef ipc_svr::Server_iface Server_iface`

*Type for abstract server interface.*

- `typedef ipc_svr::Server_iface::Demand Demand`

*Type for server-side receive buffer demand.*

### 15.466.1 Detailed Description

The IPC interface for creating ports.

The Switch factory provides an IPC interface to create ports. Ports are the only option for a client to communicate with the switch and, thus, with other network devices.

The `Switch_factory` gets constructed when the net switch application gets started. It thereafter gets registered on the switch's server to serve IPC `create` calls.

Definition at line 114 of file `main.cc`.

## 15.466.2 Member Function Documentation

### 15.466.2.1 op\_create()

```
long Switch_factory::op_create (
    L4::Factory::Rights ,
    L4::Ipc::Cap< void > & res,
    l4_umword_t type,
    L4::Ipc::Varg_list_ref va) [inline]
```

Handle factory protocol.

This function is invoked after an incoming factory::create request and creates a new port or statistics interface if possible.

Definition at line 533 of file [main.cc](#).

References [L4\\_EINVAL](#).

The documentation for this class was generated from the following file:


- pkg/virtio-net-switch/server/switch/main.cc

## 15.467 Virtio\_net Class Reference

The Base class of a Port.


```
#include <virtio_net.h>
```

Inheritance diagram for Virtio\_net:





Collaboration diagram for Virtio\_net:



## Public Member Functions

- void **reset** () override  
*reset callback, called for doing a device reset*
- int **reconfig\_queue** (unsigned index) override  
*callback for client queue-config request*
- bool **check\_features** () override

- callback for checking the subset of accepted features*
- bool **check\_queues** () override  
*Check whether both virtqueues are ready.*
- void **register\_single\_driver\_irq** () override  
*Save the `_kick_guest_irq` that the client sent via `device_notification_irq()`.*
- void **trigger\_driver\_config\_irq** () override  
*callback for triggering configuration change notification IRQ*
- void **notify\_queue** (L4virtio::Svr::Virtqueue \*queue)  
*Trigger the `_kick_guest_irq` IRQ.*
- Virtqueue \* **tx\_q** ()  
*Getter for the transmission queue.*
- Virtqueue \* **rx\_q** ()  
*Getter for the receive queue.*
- Virtqueue const \* **tx\_q** () const  
*Getter for the transmission queue.*
- Virtqueue const \* **rx\_q** () const  
*Getter for the receive queue.*

## Public Member Functions inherited from L4virtio::Svr::Device\_t< No\_custom\_data >

- virtual void **cfg\_changed** (unsigned)  
*callback for client device configuration changes*
- virtual L4::Cap< L4::Irq > **device\_notify\_irq** () const  
*callback to gather the device notification IRQ (old-style)*
- virtual void **register\_driver\_irq** (unsigned idx)  
*Callback for registering an notification IRQ (multi IRQ).*
- virtual L4::Cap< L4::Irq > **device\_notify\_irq** (unsigned idx)  
*Callback to gather the device notification IRQ (multi IRQ).*
- virtual unsigned **num\_events\_supported** () const  
*Return the highest notification index supported.*
- **Device\_t** (Dev\_config \*dev\_config)  
*Make a device for the given config.*
- Mem\_list const \* **mem\_info** () const  
*Get the memory region list used for this device.*
- void **reset\_queue\_config** (unsigned idx, unsigned num\_max, bool inc\_generation=false, unsigned device\_notify\_index=0)  
*Trigger reset for the configuration space for queue idx.*
- void **init\_mem\_info** (unsigned num)  
*Initialize the memory region list to the given maximum.*
- void **device\_error** ()  
*Transition device into `DEVICE_NEEDS_RESET` state.*
- bool **setup\_queue** (Virtqueue \*q, unsigned qn, unsigned num\_max)  
*Enable/disable the specified queue.*
- bool **handle\_mem\_cmd\_write** ()  
*Check for a value in the `cmd` register and handle a write.*
- void **enable\_trusted\_ds\_validation** ()  
*Enable trusted dataspace validation.*
- void **add\_trusted\_dataspaces** (std::shared\_ptr< Ds\_vector const > ds)  
*Provide a list of trusted dataspaces that can be used for validation.*

## Public Member Functions inherited from [L4::Epiface\\_t0](#)< [L4virtio::Device](#), [L4::Epiface](#) >

- [Type\\_info::Demand](#) **get\_buffer\_demand** () const  
*Get the server-side buffer demand based in IFACE.*
- [Cap](#)< [L4virtio::Device](#) > **obj\_cap** () const  
*Get the (typed) capability to this object.*

## Public Member Functions inherited from [L4::Epiface](#)

- **Epiface** ()  
*Make a server object.*
- virtual **~Epiface** ()=0  
*Destroy the object.*
- Stored\_cap [obj\\_cap](#) () const  
*Get the capability to the kernel object belonging to this object.*
- [Server\\_iface](#) \* **server\_iface** () const  
*Get pointer to server interface at which the object is currently registered.*
- int **set\_server** ([Server\\_iface](#) \*srv, [Cap](#)< void > cap, bool managed=false)  
*Set server registration info for the object.*
- void **set\_obj\_cap** ([Cap](#)< void > const &cap)  
*Deprecated server registration function.*

## Additional Inherited Members

## Public Types inherited from [L4::Epiface\\_t0](#)< [L4virtio::Device](#), [L4::Epiface](#) >

- typedef [L4virtio::Device](#) **Interface**  
*Data type of the IPC interface definition.*

## Public Types inherited from [L4::Epiface](#)

- typedef [lpc\\_svr::Server\\_iface](#) **Server\_iface**  
*Type for abstract server interface.*
- typedef [lpc\\_svr::Server\\_iface::Demand](#) **Demand**  
*Type for server-side receive buffer demand.*

## Protected Attributes inherited from [L4virtio::Svr::Device\\_t](#)< [No\\_custom\\_data](#) >

- **Mem\_list\_mem\_info**  
*Memory region list.*

### 15.467.1 Detailed Description

The Base class of a Port.

This class provides the Virtio network protocol specific implementation aspects of a port.

[Virtio\\_net](#) comprises the virtqueues for both, the incoming and the outgoing network requests:

- The transmission queue, containing requests to be transmitted to other ports. The transmission queue is filled by the client, this port relates to.
- The receive queue, containing requests that have been transmitted from other ports. The receive queue is filled by the switch.

Definition at line 71 of file [virtio\\_net.h](#).

### 15.467.2 Member Function Documentation

#### 15.467.2.1 notify\_queue()

```
void Virtio_net::notify_queue (
    L4virtio::Svr::Virtqueue * queue) [inline]
```

Trigger the `_kick_guest_irq` IRQ.

This function gets called on the receiving port, when a request was successfully transmitted by the switch.

Definition at line 269 of file [virtio\\_net.h](#).

References [L4VIRTIO\\_IRQ\\_STATUS\\_VRING](#).

The documentation for this class was generated from the following file:

- `pkg/virtio-net-switch/server/switch/virtio_net.h`

## 15.468 Virtio\_net\_request Class Reference

Abstraction for a network request.

```
#include <request_l4virtio.h>
```

Collaboration diagram for `Virtio_net_request`:



## Public Member Functions

- [Mac\\_addr dst\\_mac](#) () const  
*Get the Mac address of the destination port.*
- [Mac\\_addr src\\_mac](#) () const  
*Get the Mac address of the source port.*

## Static Public Member Functions

- static void [drop\\_requests](#) ([Virtio\\_net](#) \*dev, [L4virtio::Svr::Virtqueue](#) \*queue)  
*Drop all requests of a specific queue.*
- static std::optional< [Virtio\\_net\\_request](#) > [get\\_request](#) ([Virtio\\_net](#) \*dev, [L4virtio::Svr::Virtqueue](#) \*queue)  
*Construct a request from the next entry of a provided queue.*

## 15.468.1 Detailed Description

Abstraction for a network request.

A [Virtio\\_net\\_request](#) is constructed by the source port, using the static function [get\\_request](#) () as part of [Port\\_iface::get\\_tx\\_request](#) ().

On destruction, [finish](#) () will be called, which, will trigger the client IRQ of the source client.

Definition at line 35 of file [request\\_l4virtio.h](#).

## 15.468.2 Member Function Documentation

### 15.468.2.1 drop\_requests()

```
void Virtio_net_request::drop_requests (
    Virtio_net * dev,
    L4virtio::Svr::Virtqueue * queue) [inline], [static]
```

Drop all requests of a specific queue.

This function is used for example to drop all requests in the transmission queue of a monitor port, since monitor ports are not allowed to transmit data.

#### Parameters


<i>dev</i>	Port of the provided virtqueue.
<i>queue</i>	Virtqueue to drop all requests of.

Definition at line 172 of file [request\\_l4virtio.h](#).


References [L4virtio::Svr::Virtqueue::desc\\_avail](#)(), [L4virtio::Svr::Virtqueue::finish](#)(), [L4\\_UNLIKELY](#), [L4virtio::Svr::Virtqueue::next\\_avail](#)(), [L4virtio::Virtqueue::ready](#)(), and [L4virtio::Svr::Request\\_processor::start](#)().

Referenced by [L4virtio\\_port::drop\\_requests](#)().

Here is the call graph for this function:



Here is the caller graph for this function:



### 15.468.2.2 get\_request()

```

std::optional< Virtio_net_request > Virtio_net_request::get_request (
    Virtio_net * dev,
    L4virtio::Svr::Virtqueue * queue) [inline], [static]
  
```

Construct a request from the next entry of a provided queue.

#### Parameters


<i>dev</i>	Port of the provided virtqueue.
<i>queue</i>	Virtqueue to extract next entry from.

Definition at line 199 of file [request\\_l4virtio.h](#).


References [L4\\_UNLIKELY](#), [L4virtio::Svr::Virtqueue::next\\_avail\(\)](#), and [L4virtio::Virtqueue::ready\(\)](#).

Referenced by [L4virtio\\_port::get\\_tx\\_request\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



The documentation for this class was generated from the following file:


- `pkg/virtio-net-switch/server/switch/request_l4virtio.h`

## 15.469 Virtio\_switch Class Reference

The Virtio switch contains all ports and processes network requests.

```
#include <switch.h>
```

Collaboration diagram for Virtio\_switch:



## Public Member Functions

- [Virtio\\_switch](#) (unsigned max\_ports)  
*Create a switch with n ports.*
- bool [add\\_port](#) (Port\_iface \*port)  
*Add a port to the switch.*
- bool [add\\_monitor\\_port](#) (Port\_iface \*port)  
*Add a monitor port to the switch.*
- void [check\\_ports](#) ()  
*Check validity of ports.*
- bool [handle\\_l4virtio\\_port\\_tx](#) (L4virtio\_port \*port)  
*Handle TX queue of the given port.*
- bool [port\\_available](#) (bool monitor)  
*Is there still a free port on this switch available?*

### 15.469.1 Detailed Description

The Virtio switch contains all ports and processes network requests.

A Port on its own is not capable to process an incoming network request because it has no knowledge about other ports. The processing of an incoming request therefore gets delegated to the switch.

The [Virtio\\_switch](#) is constructed at the start of the Virtio Net Switch application. The factory saves a reference to it to pass it to the `Kick_irq` on port creation.

Definition at line 35 of file [switch.h](#).



## 15.469.2 Constructor & Destructor Documentation

### 15.469.2.1 Virtio\_switch()

```
Virtio_switch::Virtio_switch (  
    unsigned max_ports) [explicit]
```

Create a switch with n ports.

#### Parameters

<i>max_ports</i>	maximal number of provided ports
------------------	----------------------------------

Definition at line 12 of file [switch.cc](#).

## 15.469.3 Member Function Documentation

### 15.469.3.1 add\_monitor\_port()

```
bool Virtio_switch::add_monitor_port (  
    Port_iface * port)
```

Add a monitor port to the switch.

#### Parameters

<i>port</i>	A pointer to an already constructed Port_iface object.
-------------	--

#### Return values

<i>true</i>	Port was added successfully.
<i>false</i>	Switch was not able to add the port.

Definition at line 41 of file [switch.cc](#).

### 15.469.3.2 add\_port()

```
bool Virtio_switch::add_port (  
    Port_iface * port)
```

Add a port to the switch.

#### Parameters

<i>port</i>	A pointer to an already constructed Port_iface object.
-------------	--

**Return values**

<i>true</i>	Port was added successfully.
<i>false</i>	Switch was not able to add the port.

Definition at line 17 of file [switch.cc](#).

References [Mac\\_addr::is\\_unknown\(\)](#).

Here is the call graph for this function:

**15.469.3.3 check\_ports()**

```
void Virtio_switch::check_ports ()
```

Check validity of ports.

Check whether all ports are still used and remove any unused (unreferenced) ports. Shall be invoked after an incoming cap deletion irq to remove ports without clients.

Definition at line 56 of file [switch.cc](#).

**15.469.3.4 handle\_l4virtio\_port\_tx()**

```
bool Virtio_switch::handle_l4virtio_port_tx (
    L4virtio_port * port)
```

Handle TX queue of the given port.

**Parameters**

<i>port</i>	<a href="#">L4virtio_port</a> to handle pending TX work for.
-------------	--


**Return values**

<i>false</i>	Port hit its TX burst limit, and thus a TX pending reschedule notification was queued.
<i>true</i>	Port's entire TX queue was processed.

Definition at line 180 of file [switch.cc](#).

References [L4virtio::Svr::Device\\_t< DATA >::device\\_error\(\)](#), [L4virtio::Svr::Virtqueue::disable\\_notify\(\)](#), [L4virtio::Svr::Virtqueue::enable\\_notify\(\)](#), [L4virtio::Svr::Bad\\_descriptor::message\(\)](#), [Virtio\\_net::rx\\_q\(\)](#), [Virtio\\_net::tx\\_q\(\)](#), and [L4virtio\\_port::tx\\_work\\_pending\(\)](#).

Here is the call graph for this function:



### 15.469.3.5 port\_available()

```
bool Virtio_switch::port_available (
    bool monitor) [inline]
```

Is there still a free port on this switch available?

#### Parameters

<i>monitor</i>	True if we look for a monitor slot.
----------------	-------------------------------------

#### Return values

<i>true</i>	Port is available.
<i>false</i>	No port available.

Definition at line 146 of file [switch.h](#).

The documentation for this class was generated from the following files:


- `pkg/virtio-net-switch/server/switch/switch.h`
- `pkg/virtio-net-switch/server/switch/switch.cc`

## 15.470 Virtio\_vlan\_mangle Class Reference

Class for VLAN packet rewriting.

```
#include <vlan.h>
```

Collaboration diagram for Virtio\_vlan\_mangle:



### Public Member Functions

- [Virtio\\_vlan\\_mangle](#) ()  
*Default constructor.*
- [l4\\_uint32\\_t copy\\_pkt](#) ([Buffer](#) &dst, [Buffer](#) &src)  
*Copy packet from src to dst.*
- void [rewrite\\_hdr](#) ([Virtio\\_net::Hdr](#) \*hdr)  
*Rewrite the virtio network header.*

### Static Public Member Functions

- static constexpr [Virtio\\_vlan\\_mangle add](#) ([l4\\_uint16\\_t](#) tci)  
*Construct an object that adds a VLAN tag.*
- static constexpr [Virtio\\_vlan\\_mangle remove](#) ()  
*Construct an object that removes the VLAN tag.*

### 15.470.1 Detailed Description

Class for VLAN packet rewriting.

Definition at line 36 of file [vlan.h](#).

## 15.470.2 Constructor & Destructor Documentation

### 15.470.2.1 Virtio\_vlan\_mangle()

`Virtio_vlan_mangle::Virtio_vlan_mangle () [inline]`


Default constructor.

The packet is not touched in any way.

Definition at line 52 of file [vlan.h](#).

Referenced by [add\(\)](#), and [remove\(\)](#).

Here is the caller graph for this function:



## 15.470.3 Member Function Documentation

### 15.470.3.1 add()

```
constexpr Virtio_vlan_mangle Virtio_vlan_mangle::add (
    14_uint16_t tci) [inline], [static], [constexpr]
```

Construct an object that adds a VLAN tag.

#### Parameters


<i>tci</i>	The TCI field of the VLAN tag to add.
------------	---------------------------------------

It is the callers responsibility to ensure that the packet is not already tagged.

Definition at line 64 of file [vlan.h](#).

References [Virtio\\_vlan\\_mangle\(\)](#).

Here is the call graph for this function:



### 15.470.3.2 copy\_pkt()

```
l4_uint32_t Virtio_vlan_mangle::copy_pkt (
    Buffer & dst,
    Buffer & src) [inline]
```

Copy packet from *src* to *dst*.

#### Parameters

<i>src</i>	Source packet buffer
<i>dst</i>	Destination packet buffer

#### Returns


The number of bytes copied

Copy the data from *src* to *dst*, possibly rewriting parts of the packet. The method is expected to be called repeatedly until the source packet is finished. Partial copies are allowed (including reading nothing from the source buffer) as long as progress is made, i.e. repeatedly calling this function eventually consumes the source buffer.

Definition at line 93 of file [vlan.h](#).

References [L4virtio::Svr::Data\\_buffer::copy\\_to\(\)](#), [L4\\_LIKELY](#), [L4virtio::Svr::Data\\_buffer::left](#), [L4virtio::Svr::Data\\_buffer::pos](#), and [L4virtio::Svr::Data\\_buffer::skip\(\)](#).

Here is the call graph for this function:



### 15.470.3.3 remove()

```
constexpr Virtio_vlan_mangle Virtio_vlan_mangle::remove () [inline], [static], [constexpr]
```


Construct an object that removes the VLAN tag.

This object assumes that the Ethernet packet has a VLAN tag and will slavishly remove the necessary bytes from the packet.

Definition at line 75 of file [vlan.h](#).

References [Virtio\\_vlan\\_mangle\(\)](#).

Here is the call graph for this function:



#### 15.470.3.4 `rewrite_hdr()`

```
void Virtio_vlan_mangle::rewrite_hdr (  
    Virtio_net::Hdr * hdr) [inline]
```

Rewrite the virtio network header.

##### Parameters

<i>hdr</i>	The virtio header of the packet
------------	---------------------------------

This method is called exactly once for every virtio network packet. Any necessary changes to the header are done in-place.

Definition at line 142 of file [vlan.h](#).

References [L4\\_UNLIKELY](#).

The documentation for this class was generated from the following file:

- `pkg/virtio-net-switch/server/switch/vlan.h`





# Chapter 16

## File Documentation

### 16.1 asm\_access.h

```
00001 /*
00002  * Copyright (C) 2021, 2024 Kernkonzept GmbH.
00003  * Author(s): Jakub Jermar <jakub.jermar@kernkonzept.com>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007
00008 #pragma once
00009
00010 #include <l4/sys/l4int.h>
00011
00012 namespace Asm_access {
00013
00014     inline
00015     l4_uint8_t
00016     read(l4_uint8_t const *mem)
00017     {
00018         l4_uint8_t val;
00019
00020         asm volatile ("movb %[mem], %[val]" : [val] "=q" (val) : [mem] "m" (*mem));
00021
00022         return val;
00023     }
00024
00025     inline
00026     l4_uint16_t
00027     read(l4_uint16_t const *mem)
00028     {
00029         l4_uint16_t val;
00030
00031         asm volatile ("movw %[mem], %[val]" : [val] "=r" (val) : [mem] "m" (*mem));
00032
00033         return val;
00034     }
00035
00036     inline
00037     l4_uint32_t
00038     read(l4_uint32_t const *mem)
00039     {
00040         l4_uint32_t val;
00041
00042         asm volatile ("movl %[mem], %[val]" : [val] "=r" (val) : [mem] "m" (*mem));
00043
00044         return val;
00045     }
00046
00047     inline
00048     l4_uint64_t
00049     read(l4_uint64_t const *mem)
00050     {
00051         l4_uint64_t val;
00052
00053         asm volatile ("movq %[mem], %[val]" : [val] "=r" (val) : [mem] "m" (*mem));
00054
00055         return val;
00056     }
00057 }
```

```

00058 inline
00059 void
00060 write(l4_uint8_t val, l4_uint8_t *mem)
00061 {
00062     asm volatile ("movb %[val], %[mem]" : [mem] "=m" (*mem) : [val] "qi" (val));
00063 }
00064
00065 inline
00066 void
00067 write(l4_uint16_t val, l4_uint16_t *mem)
00068 {
00069     asm volatile ("movw %[val], %[mem]" : [mem] "=m" (*mem) : [val] "ri" (val));
00070 }
00071
00072 inline
00073 void
00074 write(l4_uint32_t val, l4_uint32_t *mem)
00075 {
00076     asm volatile ("movl %[val], %[mem]" : [mem] "=m" (*mem) : [val] "ri" (val));
00077 }
00078
00079 inline
00080 void
00081 write(l4_uint64_t val, l4_uint64_t *mem)
00082 {
00083     asm volatile ("movq %[val], %[mem]" : [mem] "=m" (*mem) : [val] "r" (val));
00084 }
00085
00086 }

```

## 16.2 asm\_access.h

```

00001 /*
00002  * Copyright (C) 2021, 2024 Kernkonzept GmbH.
00003  * Author(s): Jakub Jermar <jakub.jermar@kernkonzept.com>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007
00008 #pragma once
00009
00010 #include <l4/sys/l4int.h>
00011
00012 namespace Asm_access {
00013
00014 inline
00015 l4_uint8_t
00016 read(l4_uint8_t const *mem)
00017 {
00018     l4_uint8_t val;
00019
00020     asm volatile ("ldrb %[val], %[mem]" : [val] "=r" (val) : [mem] "m" (*mem));
00021
00022     return val;
00023 }
00024
00025 inline
00026 l4_uint16_t
00027 read(l4_uint16_t const *mem)
00028 {
00029     l4_uint16_t val;
00030
00031     asm volatile ("ldrh %[val], %[mem]" : [val] "=r" (val) : [mem] "m" (*mem));
00032
00033     return val;
00034 }
00035
00036 inline
00037 l4_uint32_t
00038 read(l4_uint32_t const *mem)
00039 {
00040     l4_uint32_t val;
00041
00042     asm volatile ("ldr %[val], %[mem]" : [val] "=r" (val) : [mem] "m" (*mem));
00043
00044     return val;
00045 }
00046
00047 inline
00048 void
00049 write(l4_uint8_t val, l4_uint8_t *mem)
00050 {
00051     asm volatile ("strb %[val], %[mem]" : [mem] "=m" (*mem) : [val] "r" (val));

```

```

00052 }
00053
00054 inline
00055 void
00056 write(l4_uint16_t val, l4_uint16_t *mem)
00057 {
00058     asm volatile ("strh %[val], %[mem]" : [mem] "=m" (*mem) : [val] "r" (val));
00059 }
00060
00061 inline
00062 void
00063 write(l4_uint32_t val, l4_uint32_t *mem)
00064 {
00065     asm volatile ("str %[val], %[mem]" : [mem] "=m" (*mem) : [val] "r" (val));
00066 }
00067
00068 }

```

## 16.3 asm\_access.h

```

00001 /*
00002  * Copyright (C) 2021, 2024 Kernkonzept GmbH.
00003  * Author(s): Jakub Jermar <jakub.jermar@kernkonzept.com>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007
00008 #pragma once
00009
00010 #include <l4/sys/l4int.h>
00011
00012 namespace Asm_access {
00013
00014 inline
00015 l4_uint8_t
00016 read(l4_uint8_t const *mem)
00017 {
00018     l4_uint8_t val;
00019
00020     asm volatile ("ldrb %w[val], %[mem]" : [val] "=r" (val) : [mem] "m" (*mem));
00021
00022     return val;
00023 }
00024
00025 inline
00026 l4_uint16_t
00027 read(l4_uint16_t const *mem)
00028 {
00029     l4_uint16_t val;
00030
00031     asm volatile ("ldrh %w[val], %[mem]" : [val] "=r" (val) : [mem] "m" (*mem));
00032
00033     return val;
00034 }
00035
00036 inline
00037 l4_uint32_t
00038 read(l4_uint32_t const *mem)
00039 {
00040     l4_uint32_t val;
00041
00042     asm volatile ("ldr %w[val], %[mem]" : [val] "=r" (val) : [mem] "m" (*mem));
00043
00044     return val;
00045 }
00046
00047 inline
00048 l4_uint64_t
00049 read(l4_uint64_t const *mem)
00050 {
00051     l4_uint64_t val;
00052
00053     asm volatile ("ldr %[val], %[mem]" : [val] "=r" (val) : [mem] "m" (*mem));
00054
00055     return val;
00056 }
00057
00058 inline
00059 void
00060 write(l4_uint8_t val, l4_uint8_t *mem)
00061 {
00062     asm volatile ("strb %w[val], %[mem]" : [mem] "=m" (*mem) : [val] "r" (val));
00063 }

```

```

00064
00065 inline
00066 void
00067 write(l4_uint16_t val, l4_uint16_t *mem)
00068 {
00069     asm volatile ("strh %w[val], %[mem]" : [mem] "=m" (*mem) : [val] "r" (val));
00070 }
00071
00072 inline
00073 void
00074 write(l4_uint32_t val, l4_uint32_t *mem)
00075 {
00076     asm volatile ("str %w[val], %[mem]" : [mem] "=m" (*mem) : [val] "r" (val));
00077 }
00078
00079 inline
00080 void
00081 write(l4_uint64_t val, l4_uint64_t *mem)
00082 {
00083     asm volatile ("str %[val], %[mem]" : [mem] "=m" (*mem) : [val] "r" (val));
00084 }
00085 }
00086 }

```

## 16.4 asm\_access.h

```

00001 /*
00002  * Copyright (C) 2021, 2024 Kernkonzept GmbH.
00003  * Author(s): Jakub Jermar <jakub.jermar@kernkonzept.com>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007
00008 #pragma once
00009
00010 #include <l4/drivers/asm_access_gen.h>

```

## 16.5 asm\_access.h

```

00001 /*
00002  * Copyright (C) 2021, 2024 Kernkonzept GmbH.
00003  * Author(s): Jakub Jermar <jakub.jermar@kernkonzept.com>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007
00008 #pragma once
00009
00010 #include <l4/drivers/asm_access_gen.h>

```

## 16.6 asm\_access.h

```

00001 /*
00002  * Copyright (C) 2021, 2024 Kernkonzept GmbH.
00003  * Author(s): Georg Kotheimer <georg.kotheimer@kernkonzept.com>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007
00008 #pragma once
00009
00010 #include <l4/sys/l4int.h>
00011
00012 namespace Asm_access {
00013
00014 inline
00015 l4_uint8_t
00016 read(l4_uint8_t const *mem)
00017 {
00018     l4_uint8_t val;
00019
00020     asm volatile ("lb %[val], %[mem]" : [val] "=r" (val) : [mem] "m" (*mem));
00021 }

```

```

00022     return val;
00023 }
00024
00025 inline
00026 l4_uint16_t
00027 read(l4_uint16_t const *mem)
00028 {
00029     l4_uint16_t val;
00030
00031     asm volatile ("lh %[val], %[mem]" : [val] "=r" (val) : [mem] "m" (*mem));
00032
00033     return val;
00034 }
00035
00036 inline
00037 l4_uint32_t
00038 read(l4_uint32_t const *mem)
00039 {
00040     l4_uint32_t val;
00041
00042     asm volatile ("lw %[val], %[mem]" : [val] "=r" (val) : [mem] "m" (*mem));
00043
00044     return val;
00045 }
00046
00047 inline
00048 void
00049 write(l4_uint8_t val, l4_uint8_t *mem)
00050 {
00051     asm volatile ("sb %[val], %[mem]" : [mem] "=m" (*mem) : [val] "r" (val));
00052 }
00053
00054 inline
00055 void
00056 write(l4_uint16_t val, l4_uint16_t *mem)
00057 {
00058     asm volatile ("sh %[val], %[mem]" : [mem] "=m" (*mem) : [val] "r" (val));
00059 }
00060
00061 inline
00062 void
00063 write(l4_uint32_t val, l4_uint32_t *mem)
00064 {
00065     asm volatile ("sw %[val], %[mem]" : [mem] "=m" (*mem) : [val] "r" (val));
00066 }
00067
00068 #if __riscv_xlen == 64
00069
00070 inline
00071 l4_uint64_t
00072 read(l4_uint64_t const *mem)
00073 {
00074     l4_uint64_t val;
00075
00076     asm volatile ("ld %[val], %[mem]" : [val] "=r" (val) : [mem] "m" (*mem));
00077
00078     return val;
00079 }
00080
00081 inline
00082 void
00083 write(l4_uint64_t val, l4_uint64_t *mem)
00084 {
00085     asm volatile ("sd %[val], %[mem]" : [mem] "=m" (*mem) : [val] "r" (val));
00086 }
00087
00088 #endif
00089
00090 }

```

## 16.7 asm\_access.h

```

00001 /*
00002  * Copyright (C) 2021, 2024 Kernkonzept GmbH.
00003  * Author(s): Jakub Jermar <jakub.jermar@kernkonzept.com>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007
00008 #pragma once
00009
00010 #include <l4/drivers/asm_access_gen.h>

```

## 16.8 asm\_access.h

```

00001 /*
00002  * Copyright (C) 2021, 2024 Kernkonzept GmbH.
00003  * Author(s): Jakub Jermar <jakub.jermar@kernkonzept.com>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007
00008 #pragma once
00009
00010 #include <l4/sys/l4int.h>
00011
00012 namespace Asm_access {
00013
00014     inline
00015     l4_uint8_t
00016     read(l4_uint8_t const *mem)
00017     {
00018         l4_uint8_t val;
00019
00020         asm volatile ("movb %[mem], %[val]" : [val] "=q" (val) : [mem] "m" (*mem));
00021
00022         return val;
00023     }
00024
00025     inline
00026     l4_uint16_t
00027     read(l4_uint16_t const *mem)
00028     {
00029         l4_uint16_t val;
00030
00031         asm volatile ("movw %[mem], %[val]" : [val] "=r" (val) : [mem] "m" (*mem));
00032
00033         return val;
00034     }
00035
00036     inline
00037     l4_uint32_t
00038     read(l4_uint32_t const *mem)
00039     {
00040         l4_uint32_t val;
00041
00042         asm volatile ("movl %[mem], %[val]" : [val] "=r" (val) : [mem] "m" (*mem));
00043
00044         return val;
00045     }
00046
00047     inline
00048     void
00049     write(l4_uint8_t val, l4_uint8_t *mem)
00050     {
00051         asm volatile ("movb %[val], %[mem]" : [mem] "=m" (*mem) : [val] "qi" (val));
00052     }
00053
00054     inline
00055     void
00056     write(l4_uint16_t val, l4_uint16_t *mem)
00057     {
00058         asm volatile ("movw %[val], %[mem]" : [mem] "=m" (*mem) : [val] "ri" (val));
00059     }
00060
00061     inline
00062     void
00063     write(l4_uint32_t val, l4_uint32_t *mem)
00064     {
00065         asm volatile ("movl %[val], %[mem]" : [mem] "=m" (*mem) : [val] "ri" (val));
00066     }
00067 }
00068

```

## 16.9 asm\_access\_gen.h

```

00001 /*
00002  * Copyright (C) 2021, 2024 Kernkonzept GmbH.
00003  * Author(s): Jakub Jermar <jakub.jermar@kernkonzept.com>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007 #pragma once
00008
00009 #include <l4/sys/l4int.h>

```

```

00010 #include <l4/cxx/type_traits>
00011
00012 namespace Asm_access {
00013
00014 template <typename T>
00015 struct is_supported_type
00016 {
00017     static const bool value = cxx::is_same<T, l4_uint8_t>::value
00018                               || cxx::is_same<T, l4_uint16_t>::value
00019                               || cxx::is_same<T, l4_uint32_t>::value
00020                               || cxx::is_same<T, l4_uint64_t>::value;
00021 };
00022
00023 template <typename T>
00024 inline
00025 typename cxx::enable_if<is_supported_type<T>::value, T>::type
00026 read(T const *mem)
00027 {
00028     return *reinterpret_cast<volatile T const *>(mem);
00029 }
00030
00031 template <typename T>
00032 inline
00033 typename cxx::enable_if<is_supported_type<T>::value, void>::type
00034 write(T val, T *mem)
00035 {
00036     *reinterpret_cast<volatile T *>(mem) = val;
00037 }
00038
00039 }

```

## 16.10 hw\_mmio\_register\_block

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00002 /*
00003  * Copyright (C) 2014-2021, 2023-2024 Kernkonzept GmbH.
00004  * Author(s): Alexander Warg <alexander.warg@kernkonzept.com>
00005  *            Sarah Hoffmann <sarah.hoffmann@kernkonzept.com>
00006  *
00007  * License: see LICENSE.spdx (in this directory or the directories above)
00008  */
00009 #pragma once
00010
00011 #include <l4/drivers/hw_register_block>
00012 #include <l4/drivers/asm_access.h>
00013
00014 namespace L4drivers {
00015
00016 class Mmio_register_block_base
00017 {
00018 protected:
00019     l4_addr_t _base;
00020     l4_addr_t _shift;
00021
00022 public:
00023     explicit Mmio_register_block_base(l4_addr_t base = 0, l4_addr_t shift = 0)
00024         : _base(base), _shift(shift) {}
00025
00026     template< typename T >
00027     T read(l4_addr_t reg) const
00028     { return Asm_access::read(reinterpret_cast<T const *>(_base + (reg « _shift))); }
00029
00030     template< typename T >
00031     void write(T value, l4_addr_t reg) const
00032     { Asm_access::write(value, reinterpret_cast<T *>(_base + (reg « _shift))); }
00033
00034     void set_base(l4_addr_t base) { _base = base; }
00035     void set_shift(l4_addr_t shift) { _shift = shift; }
00036
00037     l4_addr_t get_base() const { return _base; }
00038 };
00039
00040 template< unsigned MAX_BITS = 32 >
00041 struct Mmio_register_block
00042 : Register_block_impl<Mmio_register_block<MAX_BITS>, MAX_BITS>,
00043   Mmio_register_block_base
00044 {
00045     explicit Mmio_register_block(l4_addr_t base = 0, l4_addr_t shift = 0)
00046         : Mmio_register_block_base(base, shift) {}
00047 };
00048
00049 }
00050
00051 }
00052
00053 }

```

## 16.11 hw\_register\_block

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00002 /*
00003  * Copyright (C) 2014-2021, 2023-2024 Kernkonzept GmbH.
00004  * Author(s): Alexander Warg <alexander.warg@kernkonzept.com>
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00008 #pragma once
00009
00010 #include <l4/sys/types.h>
00011 #include <l4/cxx/type_traits>
00012
00013 namespace L4drivers {
00014
00015
00062
00063
00071 template< unsigned MAX_BITS = 32 >
00072 struct Register_block_base;
00073
00074 template<>
00075 struct Register_block_base<8>
00076 {
00077     virtual l4_uint8_t do_read_8(l4_addr_t reg) const = 0;
00078     virtual void do_write_8(l4_uint8_t value, l4_addr_t reg) = 0;
00079     virtual ~Register_block_base() = 0;
00080 };
00081
00082 inline Register_block_base<8>::~~Register_block_base() {}
00083
00084 template<>
00085 struct Register_block_base<16> : Register_block_base<8>
00086 {
00087     virtual l4_uint16_t do_read_16(l4_addr_t reg) const = 0;
00088     virtual void do_write_16(l4_uint16_t value, l4_addr_t reg) = 0;
00089 };
00090
00091 template<>
00092 struct Register_block_base<32> : Register_block_base<16>
00093 {
00094     virtual l4_uint32_t do_read_32(l4_addr_t reg) const = 0;
00095     virtual void do_write_32(l4_uint32_t value, l4_addr_t reg) = 0;
00096 };
00097
00098 template<>
00099 struct Register_block_base<64> : Register_block_base<32>
00100 {
00101     virtual l4_uint64_t do_read_64(l4_addr_t reg) const = 0;
00102     virtual void do_write_64(l4_uint64_t value, l4_addr_t reg) = 0;
00103 };
00104 #undef REGBLK_READ_TEMPLATE
00105 #undef REGBLK_WRITE_TEMPLATE
00106
00107 template<typename CHILD>
00108 struct Register_block_modify_mixin
00109 {
00110     template< typename T >
00111     T modify(T clear_bits, T set_bits, l4_addr_t reg) const
00112     {
00113         CHILD const *c = static_cast<CHILD const *>(this);
00114         T r = (c->template read<T>(reg) & ~clear_bits) | set_bits;
00115         c->template write<T>(r, reg);
00116         return r;
00117     }
00118
00119     template< typename T >
00120     T set(T set_bits, l4_addr_t reg) const
00121     { return this->template modify<T>(T(0), set_bits, reg); }
00122
00123     template< typename T >
00124     T clear(T clear_bits, l4_addr_t reg) const
00125     { return this->template modify<T>(clear_bits, T(0), reg); }
00126 };
00127
00128
00129 #define REGBLK_READ_TEMPLATE(sz) \
00130     template< typename T > \
00131     typename cxx::enable_if<sizeof(T) == (sz / 8), T>::type read(l4_addr_t reg) const \
00132     { \
00133         union X { T t; l4_uint##sz##_t v; } m; \
00134         m.v = _b->do_read_##sz (reg); \
00135         return m.t; \
00136     }
00137

```



```

00138 #define REGBLK_WRITE_TEMPLATE(sz) \
00139     template< typename T > \
00140     void write(T value, l4_addr_t reg, typename cxx::enable_if<sizeof(T) == (sz / 8), T>::type = T())
00141     const \
00142     { \
00143         union X { T t; l4_uint##sz##_t v; } m; \
00144         m.t = value; \
00145         _b->do_write_##sz(m.v, reg); \
00146     }
00147
00155 template< typename BLOCK >
00156 class Register_block_tmpl
00157 : public Register_block_modify_mixin<Register_block_tmpl<BLOCK> >
00158 {
00159 private:
00160     BLOCK *_b;
00161
00162 public:
00163     Register_block_tmpl(BLOCK *blk) : _b(blk) {}
00164     Register_block_tmpl() = default;
00165
00166     operator BLOCK * () const { return _b; }
00167
00168     REGBLK_READ_TEMPLATE(8)
00169     REGBLK_WRITE_TEMPLATE(8)
00170     REGBLK_READ_TEMPLATE(16)
00171     REGBLK_WRITE_TEMPLATE(16)
00172     REGBLK_READ_TEMPLATE(32)
00173     REGBLK_WRITE_TEMPLATE(32)
00174     REGBLK_READ_TEMPLATE(64)
00175     REGBLK_WRITE_TEMPLATE(64)
00176 };
00177
00178 #undef REGBLK_READ_TEMPLATE
00179 #undef REGBLK_WRITE_TEMPLATE
00180
00181 namespace __Type_helper {
00182     template<unsigned> struct Unsigned;
00183     template<> struct Unsigned<8> { typedef l4_uint8_t type; };
00184     template<> struct Unsigned<16> { typedef l4_uint16_t type; };
00185     template<> struct Unsigned<32> { typedef l4_uint32_t type; };
00186     template<> struct Unsigned<64> { typedef l4_uint64_t type; };
00187 };
00188
00189
00190
00200 template< unsigned BITS, typename BLOCK >
00201 class Ro_register_tmpl
00202 {
00203 protected:
00204     BLOCK _b;
00205     unsigned _o;
00206
00207 public:
00208     typedef typename __Type_helper::Unsigned<BITS>::type value_type;
00209
00210     Ro_register_tmpl(BLOCK const &blk, unsigned offset) : _b(blk), _o(offset) {}
00211     Ro_register_tmpl() = default;
00212
00213     operator value_type () const
00214     { return _b.template read<value_type>(_o); }
00215
00216     value_type read() const
00217     { return _b.template read<value_type>(_o); }
00218 };
00219
00220
00221
00222
00223
00224
00225
00226
00227
00228
00229
00230
00231
00232
00233
00234
00235
00236 template< unsigned BITS, typename BLOCK >
00237 class Register_tmpl : public Ro_register_tmpl<BITS, BLOCK>
00238 {
00239 public:
00240     typedef typename Ro_register_tmpl<BITS, BLOCK>::value_type value_type;
00241
00242     Register_tmpl(BLOCK const &blk, unsigned offset)
00243     : Ro_register_tmpl<BITS, BLOCK>(blk, offset)
00244     {}
00245
00246     Register_tmpl() = default;
00247
00248     Register_tmpl &operator = (value_type val)
00249     { this->_b.template write<value_type>(val, this->_o); return *this; }
00250
00251     void write(value_type val)
00252     { this->_b.template write<value_type>(val, this->_o); }
00253
00254     value_type set(value_type set_bits)
00255     { return this->_b.template set<value_type>(set_bits, this->_o); }

```

```

00276
00290 value_type clear(value_type clear_bits)
00291 { return this->_b.template clear<value_type>(clear_bits, this->_o); }
00292
00308 value_type modify(value_type clear_bits, value_type set_bits)
00309 { return this->_b.template modify<value_type>(clear_bits, set_bits, this->_o); }
00310 };
00311
00312
00324 template<
00325     unsigned MAX_BITS,
00326     typename BLOCK = Register_block_tmpl<
00327         Register_block_base<MAX_BITS>
00328     >
00329 >
00330 class Register_block
00331 {
00332 private:
00333     template< unsigned B, typename BLK > friend class Register_block;
00334     template< unsigned B, typename BLK > friend class Ro_register_block;
00335     typedef BLOCK Block;
00336     Block _b;
00337
00338 public:
00339     Register_block() = default;
00340     Register_block(Block const &blk) : _b(blk) {}
00341     Register_block &operator = (Block const &blk)
00342     { _b = blk; return *this; }
00343
00344     template< unsigned BITS >
00345     Register_block(Register_block<BITS> blk) : _b(blk._b) {}
00346
00347     typedef Register_tmpl<MAX_BITS, Block> Register;
00348     typedef Ro_register_tmpl<MAX_BITS, Block> Ro_register;
00349
00356     template< unsigned BITS >
00357     Ro_register_tmpl<BITS, Block> r(unsigned offset) const
00358     { return Ro_register_tmpl<BITS, Block>(this->_b, offset); }
00359
00365     Ro_register operator [] (unsigned offset) const
00366     { return this->r<MAX_BITS>(offset); }
00367
00375     template< unsigned BITS >
00376     Register_tmpl<BITS, Block> r(unsigned offset)
00377     { return Register_tmpl<BITS, Block>(this->_b, offset); }
00378
00385     Register operator [] (unsigned offset)
00386     { return this->r<MAX_BITS>(offset); }
00387 };
00388
00398 template<
00399     unsigned MAX_BITS,
00400     typename BLOCK = Register_block_tmpl<
00401         Register_block_base<MAX_BITS> const
00402     >
00403 >
00404 class Ro_register_block
00405 {
00406 private:
00407     template< unsigned B, typename BLK > friend class Ro_register_block;
00408     typedef BLOCK Block;
00409     Block _b;
00410
00411 public:
00412     Ro_register_block() = default;
00413     Ro_register_block(BLOCK const &blk) : _b(blk) {}
00414
00415     template< unsigned BITS >
00416     Ro_register_block(Register_block<BITS> const &blk) : _b(blk._b) {}
00417
00418     typedef Ro_register_tmpl<MAX_BITS, Block> Ro_register;
00419     typedef Ro_register Register;
00420
00426     Ro_register operator [] (unsigned offset) const
00427     { return Ro_register(this->_b, offset); }
00428
00435     template< unsigned BITS >
00436     Ro_register_tmpl<BITS, Block> r(unsigned offset) const
00437     { return Ro_register_tmpl<BITS, Block>(this->_b, offset); }
00438 };
00439
00440
00454 template< typename BASE, unsigned MAX_BITS = 32 >
00455 struct Register_block_impl;
00456
00457 #define REGBLK_IMPL_RW_TEMPLATE(sz, ...) \

```

```

00458     l4_uint##sz##_t do_read_##sz(l4_addr_t reg) const override \
00459     { return static_cast<BASE const *>(this)->template read<l4_uint##sz##_t>(reg); } \
00460     \
00461     void do_write_##sz(l4_uint##sz##_t value, l4_addr_t reg) override \
00462     { static_cast<BASE*>(this)->template write<l4_uint##sz##_t>(value, reg); }
00463
00464
00465 template< typename BASE >
00466 struct Register_block_impl<BASE, 8> : public Register_block_base<8>
00467 {
00468     REGBLK_IMPL_RW_TEMPLATE(8);
00469 };
00470
00471 template< typename BASE >
00472 struct Register_block_impl<BASE, 16> : public Register_block_base<16>
00473 {
00474     REGBLK_IMPL_RW_TEMPLATE(8);
00475     REGBLK_IMPL_RW_TEMPLATE(16);
00476 };
00477
00478 template< typename BASE >
00479 struct Register_block_impl<BASE, 32> : public Register_block_base<32>
00480 {
00481     REGBLK_IMPL_RW_TEMPLATE(8);
00482     REGBLK_IMPL_RW_TEMPLATE(16);
00483     REGBLK_IMPL_RW_TEMPLATE(32);
00484 };
00485
00486 template< typename BASE >
00487 struct Register_block_impl<BASE, 64> : public Register_block_base<64>
00488 {
00489     REGBLK_IMPL_RW_TEMPLATE(8);
00490     REGBLK_IMPL_RW_TEMPLATE(16);
00491     REGBLK_IMPL_RW_TEMPLATE(32);
00492     REGBLK_IMPL_RW_TEMPLATE(64);
00493 };
00494
00495 #undef REGBLK_IMPL_RW_TEMPLATE
00496
00497 }

```

## 16.12 io\_regblock.h

```

00001 /*
00002  * Copyright (C) 2012 Technische Universität Dresden.
00003  * Author(s): Adam Lackorzynski <adam@os.inf.tu-dresden.de>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007 #pragma once
00008
00009 namespace L4
00010 {
00011     class Io_register_block
00012     {
00013     public:
00017         virtual unsigned char read8(unsigned long reg) const = 0;
00018
00022         virtual unsigned short read16(unsigned long reg) const = 0;
00023
00027         virtual unsigned int read32(unsigned long reg) const = 0;
00028
00029         /*
00030          * \brief Read register with an 8 byte access.
00031          */
00032         //virtual unsigned long long read64(unsigned long reg) const = 0;
00033
00037         virtual void write8(unsigned long reg, unsigned char value) const = 0;
00038
00042         virtual void write16(unsigned long reg, unsigned short value) const = 0;
00043
00047         virtual void write32(unsigned long reg, unsigned int value) const = 0;
00048
00049         /*
00050          * \brief Write register with an 8 byte access.
00051          */
00052         //virtual void write64(unsigned long reg, unsigned long long value) const = 0;
00053
00057         virtual unsigned long addr(unsigned long reg) const = 0;
00058
00064         virtual void delay() const = 0;
00065
00066         virtual ~Io_register_block() = 0;

```

```

00067
00075     template< typename R >
00076     R read(unsigned long reg) const
00077     {
00078         static_assert(sizeof(R) == 1 || sizeof(R) == 2 || sizeof(R) == 4,
00079             "Invalid size");
00080
00081         switch (sizeof(R))
00082         {
00083             case 1: return read8(reg);
00084             case 2: return read16(reg);
00085             case 4: return read32(reg);
00086         };
00087     }
00088
00096     template< typename R >
00097     void write(unsigned long reg, R value) const
00098     {
00099         static_assert(sizeof(R) == 1 || sizeof(R) == 2 || sizeof(R) == 4,
00100             "Invalid size");
00101
00102         switch (sizeof(R))
00103         {
00104             case 1: write8(reg, value); return;
00105             case 2: writel6(reg, value); return;
00106             case 4: write32(reg, value); return;
00107         };
00108     }
00109
00120     template< typename R >
00121     R modify(unsigned long reg, R clear_bits, R set_bits) const
00122     {
00123         R r = (read<R>(reg) & ~clear_bits) | set_bits;
00124         write(reg, r);
00125         return r;
00126     }
00127
00134     template< typename R >
00135     R set(unsigned long reg, R set_bits) const
00136     {
00137         return modify<R>(reg, 0, set_bits);
00138     }
00139
00146     template< typename R >
00147     R clear(unsigned long reg, R clear_bits) const
00148     {
00149         return modify<R>(reg, clear_bits, 0);
00150     }
00151 };
00152
00153 inline Io_register_block::~Io_register_block() {}
00154
00155
00156
00157 class Io_register_block_mmio : public Io_register_block
00158 {
00159 private:
00160     template< typename R >
00161     R _read(unsigned long reg) const
00162     { return *reinterpret_cast<volatile R*>(_base + (reg << _shift)); }
00163
00164     template< typename R >
00165     void _write(unsigned long reg, R val) const
00166     { *reinterpret_cast<volatile R*>(_base + (reg << _shift)) = val; }
00167
00168 public:
00169     Io_register_block_mmio(unsigned long base, unsigned char shift = 0)
00170     : _base(base), _shift(shift)
00171     {}
00172
00173     unsigned long addr(unsigned long reg) const override
00174     { return _base + (reg << _shift); }
00175
00176     unsigned char read8(unsigned long reg) const override
00177     { return _read<unsigned char>(reg); }
00178     unsigned short read16(unsigned long reg) const override
00179     { return _read<unsigned short>(reg); }
00180     unsigned int read32(unsigned long reg) const override
00181     { return _read<unsigned int>(reg); }
00182
00183     void write8(unsigned long reg, unsigned char val) const override
00184     { _write(reg, val); }
00185     void writel6(unsigned long reg, unsigned short val) const override
00186     { _write(reg, val); }
00187     void write32(unsigned long reg, unsigned int val) const override
00188     { _write(reg, val); }
00189

```

```

00190     void delay() const override
00191     {}
00192
00193     void set_base(unsigned long base) { _base = base; }
00194     void set_shift(unsigned char shift) { _shift = shift; }
00195
00196     unsigned long get_base() const { return _base; }
00197
00198 private:
00199     unsigned long _base;
00200     unsigned char _shift;
00201 };
00202
00203 template<typename ACCESS_TYPE>
00204 class Io_register_block_mmio_fixed_width : public Io_register_block
00205 {
00206 private:
00207     template< typename R >
00208     R _read(unsigned long reg) const
00209     { return *reinterpret_cast<volatile ACCESS_TYPE *>(_base + (reg « _shift)); }
00210
00211     template< typename R >
00212     void _write(unsigned long reg, R val) const
00213     { *reinterpret_cast<volatile ACCESS_TYPE *>(_base + (reg « _shift)) = val; }
00214
00215 public:
00216     Io_register_block_mmio_fixed_width(unsigned long base, unsigned char shift = 0)
00217     : _base(base), _shift(shift)
00218     {}
00219
00220     unsigned long addr(unsigned long reg) const
00221     { return _base + (reg « _shift); }
00222
00223     unsigned char read8(unsigned long reg) const override
00224     { return _read<unsigned char>(reg); }
00225     unsigned short read16(unsigned long reg) const override
00226     { return _read<unsigned short>(reg); }
00227     unsigned int read32(unsigned long reg) const override
00228     { return _read<unsigned int>(reg); }
00229
00230     void write8(unsigned long reg, unsigned char val) const override
00231     { _write(reg, val); }
00232     void write16(unsigned long reg, unsigned short val) const override
00233     { _write(reg, val); }
00234     void write32(unsigned long reg, unsigned int val) const override
00235     { _write(reg, val); }
00236
00237     void delay() const override
00238     {}
00239
00240 private:
00241     unsigned long _base;
00242     unsigned char _shift;
00243 };
00244 }

```

## 16.13 io\_regblock\_port.h

```

00001 /*
00002  * Copyright (C) 2012 Technische Universität Dresden.
00003  * Author(s): Adam Lackorzynski <adam@os.inf.tu-dresden.de>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007 #pragma once
00008
00009 #include "io_regblock.h"
00010
00011 namespace L4
00012 {
00013     class Io_register_block_port : public Io_register_block
00014     {
00015     public:
00016         Io_register_block_port(unsigned long base)
00017         : _base(base)
00018         {}
00019
00020         unsigned long addr(unsigned long reg) const override { return _base + reg; }
00021
00022         unsigned char read8(unsigned long reg) const override
00023         {
00024             unsigned char val;
00025             asm volatile("inb %w1, %b0" : "=a" (val) : "Nd" (_base + reg));

```

```

00026     return val;
00027 }
00028
00029 unsigned short read16(unsigned long reg) const override
00030 {
00031     unsigned short val;
00032     asm volatile("inw %w1, %w0" : "=a" (val) : "Nd" (_base + reg));
00033     return val;
00034 }
00035
00036 unsigned int read32(unsigned long reg) const override
00037 {
00038     unsigned int val;
00039     asm volatile("in %w1, %0" : "=a" (val) : "Nd" (_base + reg));
00040     return val;
00041 }
00042
00043 void write8(unsigned long reg, unsigned char val) const override
00044 { asm volatile("outb %b0, %w1" : : "a" (val), "Nd" (_base + reg)); }
00045
00046 void write16(unsigned long reg, unsigned short val) const override
00047 { asm volatile("outw %w0, %w1" : : "a" (val), "Nd" (_base + reg)); }
00048
00049 void write32(unsigned long reg, unsigned int val) const override
00050 { asm volatile("out %0, %w1" : : "a" (val), "Nd" (_base + reg)); }
00051
00052 void delay() const override
00053 { asm volatile ("outb %al,$0x80"); }
00054
00055 private:
00056     unsigned long _base;
00057 };
00058 }

```

## 16.14 poll\_timeout\_counter.h

```

00001 /*
00002  * Copyright (C) 2012 Technische Universität Dresden.
00003  * Author(s): Adam Lackorzynski <adam@os.inf.tu-dresden.de>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007 #pragma once
00008
00009 namespace L4 {
00010
00011     00034 class Poll_timeout_counter
00012     {
00013     public:
00042     Poll_timeout_counter(unsigned counter_val)
00014     {
00043     {
00044     set(counter_val);
00045     }
00046
00053     void set(unsigned counter_val)
00015     {
00054     {
00055     _c = counter_val;
00056     }
00057
00061     bool test(bool expression = true)
00016     {
00062     {
00063     if (!expression)
00064     return false;
00065
00066     if (_c)
00067     {
00068     --_c;
00069     return true;
00070     }
00071
00072     return false;
00073     }
00074
00081     bool timed_out() const { return _c == 0; }
00075
00082
00083 private:
00084     unsigned _c;
00085 };
00086
00087 }

```

## 16.15 device.h

```

00001 #pragma once
00002
00003 #include <stdint.h>
00004
00005 struct l4re_device_spec_dt_ids
00006 {
00007     const char *compatible;
00008 };
00009
00010 struct l4re_device_spec_pcidev_pciids
00011 {
00012     uint16_t vendor;
00013     uint16_t function;
00014 };
00015
00016 struct l4re_device_spec_pcidev_ids
00017 {
00018     struct l4re_device_spec_pcidev_pciids *pcidevs;
00019 };
00020
00021 struct l4re_device_ids
00022 {
00023     struct l4re_device_spec_dt_ids *dt = nullptr;
00024     struct l4re_device_spec_pcidev_ids *pcidev = nullptr;
00025 };
00026
00027 // ---- Internal device
00028 namespace L4 {
00029
00030     class Dev_obj
00031     {
00032     };
00033
00034 }
00035
00036 struct l4re_device_type_base
00037 {
00038     virtual L4::Dev_obj *create(void *obj_mem, unsigned arg1) = 0;
00039     virtual unsigned obj_size() = 0;
00040     virtual const l4re_device_ids *ids() = 0;
00041 };
00042
00043 #include <stdio.h>
00044 #include <string.h>
00045
00046 static inline
00047 L4::Dev_obj *
00048 l4re_dev_create_by_dt_compatible(const char *dt_compatible,
00049                                 void *obj_store, unsigned obj_store_size,
00050                                 unsigned arg1)
00051 {
00052     l4re_device_type_base *device = nullptr;
00053
00054     extern l4re_device_type_base *__L4RE_DEVICE_BEGIN[];
00055     extern l4re_device_type_base *__L4RE_DEVICE_END[];
00056
00057     for (auto const *d = __L4RE_DEVICE_BEGIN; d < __L4RE_DEVICE_END; ++d)
00058     {
00059         const l4re_device_ids *ids = (*d)->ids();
00060         if (ids->dt)
00061             for (l4re_device_spec_dt_ids *dt_id = ids->dt; dt_id->compatible; ++dt_id)
00062                 if (!strcmp(dt_compatible, dt_id->compatible))
00063                 {
00064                     device = *d;
00065                     break;
00066                 }
00067     }
00068
00069     if (!device)
00070         return nullptr;
00071
00072     if (device->obj_size() > obj_store_size)
00073         return nullptr;
00074
00075     return device->create(reinterpret_cast<void *>(obj_store), arg1);
00076 }
00077
00078 #define l4re_register_device(Device_class_base, Device_class, \
00079                             instance_name, __ids) \
00080     struct l4re_device_type_##instance_name \
00081     : public l4re_device_type_base \
00082     { \
00083         Device_class_base *create(void *objmem, unsigned arg1) override \
00084         { return new (objmem) Device_class(arg1); } \

```

```

00085     \
00086     unsigned obj_size() override { return sizeof(Device_class); } \
00087     const l4re_device_ids *ids() override { return &__ids; } \
00088 }; \
00089 static const l4re_device_type_##instance_name \
00090     l4re_device_inst_##instance_name; \
00091 static const l4re_device_type_base * const \
00092     __attribute__((section(".data.l4redevice"),used)) \
00093     l4re_device_inst_p_##instance_name \
00094     = &l4re_device_inst_##instance_name

```

## 16.16 uart\_16550.h

```

00001 /*
00002  * Copyright (C) 2008-2021 Technische Universität Dresden.
00003  * Copyright (C) 2023-2025 Kernkonzept GmbH.
00004  * Author(s): Adam Lackorzynski <adam@os.inf.tu-dresden.de>
00005  *             Alexander Warg <alexander.warg@os.inf.tu-dresden.de>
00006  *
00007  * License: see LICENSE.spdx (in this directory or the directories above)
00008  */
00009 #pragma once
00010
00011 #include "uart_base.h"
00012
00013 namespace L4 {
00014
00015 class Uart_16550 : public Uart
00016 {
00017 protected:
00018     enum Registers
00019     {
00020         TRB      = 0x00, // Transmit/Receive Buffer (read/write)
00021         BRD_LOW  = 0x00, // Baud Rate Divisor LSB if bit 7 of LCR is set (read/write)
00022         IER      = 0x01, // Interrupt Enable Register (read/write)
00023         BRD_HIGH = 0x01, // Baud Rate Divisor MSB if bit 7 of LCR is set (read/write)
00024         IIR      = 0x02, // Interrupt Identification Register (read only)
00025         FCR      = 0x02, // 16550 FIFO Control Register (write only)
00026         LCR      = 0x03, // Line Control Register (read/write)
00027         MCR      = 0x04, // Modem Control Register (read/write)
00028         LSR      = 0x05, // Line Status Register (read only)
00029         MSR      = 0x06, // Modem Status Register (read only)
00030         SPR      = 0x07, // Scratch Pad Register (read/write)
00031     };
00032
00033     enum Register_value_iir
00034     {
00035         IIR_BUSY = 7,
00036     };
00037
00038     enum Register_value_lsr
00039     {
00040         LSR_DR      = 0x01, // Receiver data ready
00041         LSR_THRE     = 0x20, // Transmit hold register empty
00042         LSR_TSRE     = 0x40, // Transmitter empty
00043     };
00044
00045     enum Init_values
00046     {
00047         #ifndef UART_16550_INIT_MCR
00048             Init_mcr = UART_16550_INIT_MCR,
00049         #else
00050             Init_mcr = 0,
00051         #endif
00052         #ifndef UART_16550_INIT_IER
00053             Init_ier = UART_16550_INIT_IER,
00054         #else
00055             Init_ier = 0,
00056         #endif
00057         #ifndef UART_16550_INIT_FCR
00058             Init_fcr = UART_16550_INIT_FCR,
00059         #else
00060             Init_fcr = 0,
00061         #endif
00062     };
00063
00064 public:
00065     enum
00066     {
00067         PAR_NONE = 0x00,
00068         PAR_EVEN = 0x18,
00069         PAR_ODD  = 0x08,
00070         DAT_5     = 0x00,

```



```

00071     DAT_6     = 0x01,
00072     DAT_7     = 0x02,
00073     DAT_8     = 0x03,
00074     STOP_1    = 0x00,
00075     STOP_2    = 0x04,
00076
00077     MODE_8N1 = PAR_NONE | DAT_8 | STOP_1,
00078     MODE_7E1 = PAR_EVEN | DAT_7 | STOP_1,
00079
00080     // these two values are to leave either mode
00081     // or baud rate unchanged on a call to change_mode
00082     MODE_NC   = 0x1000000,
00083     BAUD_NC   = 0x1000000,
00084
00085     Base_rate_x86 = 115200,
00086     Base_rate_pxa = 921600,
00087 };
00088
00089 explicit Uart_16550(unsigned long base_rate, unsigned char init_flags = 0,
00090                    unsigned char ier_bits = Init_ier,
00091                    unsigned char mcr_bits = Init_mcr,
00092                    unsigned char fcr_bits = Init_fcr)
00093 : _base_rate(base_rate), _init_flags(init_flags), _mcr_bits(mcr_bits),
00094   _ier_bits(ier_bits), _fcr_bits(fcr_bits)
00095 {}
00096
00097 bool startup(Io_register_block const *regs) override;
00098 void shutdown() override;
00099 bool change_mode(Transfer_mode m, Baud_rate r) override;
00100 int tx_avail() const;
00101 void wait_tx_done() const;
00102 inline void out_char(char c) const;
00103 int write(char const *s, unsigned long count,
00104          bool blocking = true) const override;
00105
00106 #ifndef UART_WITHOUT_INPUT
00107 bool enable_rx_irq(bool enable = true) override;
00108 int char_avail() const override;
00109 int get_char(bool blocking = true) const override;
00110 #endif
00111
00112 private:
00113 unsigned long _base_rate;
00114 unsigned char _init_flags;
00115 unsigned char _mcr_bits;
00116 unsigned char _ier_bits;
00117 unsigned char _fcr_bits;
00118 };
00119
00120 } // namespace L4

```

## 16.17 uart\_16550\_dw.h

```

00001 /*
00002  * Copyright (C) 2015 Technische Universität Dresden.
00003  * Copyright (C) 2023-2025 Kernkonzept GmbH.
00004  * Author(s): Adam Lackorzynski <adam@l4re.org>
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00008 #pragma once
00009
00010 #include "uart_16550.h"
00011
00012 namespace L4 {
00013
00014 class Uart_16550_dw : public Uart_16550
00015 {
00016 public:
00017     explicit Uart_16550_dw(unsigned long base_rate)
00018     : Uart_16550(base_rate)
00019     {}
00020
00021 #ifndef UART_WITHOUT_INPUT
00022     void irq_ack() override;
00023 #endif
00024 };
00025
00026 } // namespace L4

```

## 16.18 uart\_apb.h

```

00001 /*
00002  * Copyright (C) 2017, 2019, 2023-2025 Kernkonzept GmbH.
00003  * Author(s): Georg Kotheimer <georg.kotheimer@kernkonzept.com>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007 #pragma once
00008
00009 #include "uart_base.h"
00010
00011 namespace L4 {
00012
00017 class Uart_apb : public Uart
00018 {
00019 public:
00021   Uart_apb(unsigned freq) : _freq(freq) {}
00022   bool startup(Io_register_block const *) override;
00023   void shutdown() override;
00024   bool change_mode(Transfer_mode m, Baud_rate r) override;
00025   int tx_avail() const;
00026   void wait_tx_done() const;
00027   inline void out_char(char c) const;
00028   int write(char const *s, unsigned long count,
00029             bool blocking = true) const override;
00030
00031 #ifndef UART_WITHOUT_INPUT
00032   bool enable_rx_irq(bool enable) override;
00033   int char_avail() const override;
00034   int get_char(bool blocking = true) const override;
00035 #endif
00036
00037 private:
00038   void set_rate(Baud_rate r);
00039   unsigned _freq;
00040 };
00041
00042 } // namespace L4

```

## 16.19 uart\_base.h

```

00001 /*
00002  * Copyright (C) 2009-2012 Technische Universität Dresden.
00003  * Copyright (C) 2023-2025 Kernkonzept GmbH.
00004  * Author(s): Adam Lackorzynski <adam@os.inf.tu-dresden.de>
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00008 #pragma once
00009
00010 #include <stddef.h>
00011 #include <l4/drivers/io_regblock.h>
00012
00013 #include <l4/drivers/device.h>
00014 #include "poll_timeout_counter.h"
00015
00016 namespace L4 {
00017
00021 class Uart : public Dev_obj
00022 {
00023 protected:
00024   unsigned _mode;
00025   unsigned _rate;
00026   Io_register_block const *_regs;
00027
00028 public:
00029   void *operator new (size_t, void *p) { return p; }
00030
00031 public:
00032   typedef unsigned Transfer_mode;
00033   typedef unsigned Baud_rate;
00034
00035   Uart()
00036   : _mode(~0U), _rate(~0U)
00037   {}
00038
00046   virtual bool startup(Io_register_block const *regs) = 0;
00047
00048   virtual ~Uart() {}
00049
00053   virtual void shutdown() = 0;

```

```

00054
00066 virtual bool change_mode(Transfer_mode m, Baud_rate r) = 0;
00067
00078 virtual int write(char const *s, unsigned long count,
00079                  bool blocking = true) const = 0;
00080
00086 Transfer_mode mode() const { return _mode; }
00087
00093 Baud_rate rate() const { return _rate; }
00094
00095 #ifndef UART_WITHOUT_INPUT
00096
00104 virtual bool enable_rx_irq(bool = true) { return false; }
00105
00109 virtual void irq_ack() {}
00110
00117 virtual int char_avail() const = 0;
00118
00127 virtual int get_char(bool blocking = true) const = 0;
00128
00129 #endif // !UART_WITHOUT_INPUT
00130
00131 protected:
00143 template <typename Uart_driver, bool Timeout_guard = true>
00144 int generic_write(char const *s, unsigned long count,
00145                  bool blocking = true) const
00146 {
00147     auto *self = static_cast<Uart_driver const*>(this);
00148
00149     unsigned long c;
00150     for (c = 0; c < count; ++c)
00151     {
00152         if (!blocking && !self->tx_avail())
00153             break;
00154
00155         if constexpr (Timeout_guard)
00156         {
00157             Poll_timeout_counter i(3000000);
00158             while (i.test(!self->tx_avail()))
00159                 ;
00160         }
00161         else
00162         {
00163             while (!self->tx_avail())
00164                 ;
00165         }
00166
00167         self->out_char(*s++);
00168     }
00169
00170     if (blocking)
00171         self->wait_tx_done();
00172
00173     return c;
00174 }
00175 };
00176
00177 } // namespace L4
00178
00179 /*
00180 * Instantiate a UART, given the memory.
00181 */
00182 static inline
00183 L4::Uart *
00184 l4re_dev_uart_create_by_dt_compatible(const char *dt_compatible,
00185                                       void *obj_buf, unsigned obj_buf_size,
00186                                       unsigned freq)
00187 {
00188     L4::Dev_obj *dev = l4re_dev_create_by_dt_compatible(dt_compatible,
00189                                                         obj_buf, obj_buf_size,
00190                                                         freq);
00191     return static_cast<L4::Uart *>(dev);
00192 }
00193
00194 /*
00195 * Instantiate a UART a single time, use an internal static buffer.
00196 */
00197 static inline
00198 L4::Uart *
00199 l4re_dev_uart_create_by_dt_compatible_once(const char *dt_compatible, unsigned freq)
00200 {
00201     static bool once_done = false;
00202
00203     if (once_done)
00204         return nullptr;
00205
00206     static char __attribute__((aligned(sizeof(long) * 2))) obj_buf[64];

```

```

00207     L4::Uart *uart
00208     = l4re_dev_uart_create_by_dt_compatible(dt_compatible,
00209                                             obj_buf, sizeof(obj_buf),
00210                                             freq);
00211     if (uart)
00212         once_done = true;
00213     return uart;
00214 }
00215
00216 #define l4re_register_device_uart(Device_class, instance_name, \
00217                                 device_dt_ids, pci_ids) \
00218     static const struct l4re_device_ids __dev_spec_##instance_name \
00219     = { .dt = device_dt_ids, .pcidev = pci_ids }; \
00220     l4re_register_device(L4::Uart, Device_class, instance_name, \
00221                         __dev_spec_##instance_name)
00222
00223 #define l4re_register_device_uart_dt(Device_class, instance_name, dt_ids) \
00224     l4re_register_device_uart(Device_class, instance_name, dt_ids, nullptr)
00225
00226 #define l4re_register_device_uart_pci(Device_class, instance_name, pci_ids) \
00227     l4re_register_device_uart(Device_class, instance_name, nullptr, pci_ids)
00228
00229

```

## 16.20 uart\_cadence.h

```

00001 /*
00002  * Copyright (C) 2013 Technische Universität Dresden.
00003  * Copyright (C) 2023-2025 Kernkonzept GmbH.
00004  * Author(s): Adam Lackorzynski <adam@os.inf.tu-dresden.de>
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00008 #pragma once
00009
00010 #include "uart_base.h"
00011
00012 namespace L4 {
00013
00014     class Uart_cadence : public Uart
00015     {
00016     public:
00017         explicit Uart_cadence(unsigned base_rate) : _base_rate(base_rate) {}
00018         bool startup(Io_register_block const *) override;
00019         void shutdown() override;
00020         bool change_mode(Transfer_mode m, Baud_rate r) override;
00021         int tx_avail() const;
00022         void wait_tx_done() const {}
00023         inline void out_char(char c) const;
00024         int write(char const *s, unsigned long count,
00025                  bool blocking = true) const override;
00026
00027         #ifndef UART_WITHOUT_INPUT
00028             bool enable_rx_irq(bool) override;
00029             void irq_ack() override;
00030             int char_avail() const override;
00031             int get_char(bool blocking = true) const override;
00032         #endif
00033
00034     private:
00035         unsigned _base_rate;
00036     };
00037
00038 } // namespace L4

```

## 16.21 uart\_dcc-v6.h

```

00001 /*
00002  * Copyright (C) 2009 Technische Universität Dresden.
00003  * Copyright (C) 2023-2025 Kernkonzept GmbH.
00004  * Author(s): Adam Lackorzynski <adam@os.inf.tu-dresden.de>
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00008 #pragma once
00009
00010 #include "uart_base.h"
00011

```

```

00012 namespace L4 {
00013
00014 class Uart_dcc_v6 : public Uart
00015 {
00016 public:
00017     explicit Uart_dcc_v6() {}
00018     explicit Uart_dcc_v6(unsigned /*base_rate*/) {}
00019     bool startup(Io_register_block const *) override;
00020     void shutdown() override;
00021     bool change_mode(Transfer_mode m, Baud_rate r) override;
00022     int tx_avail() const;
00023     void wait_tx_done() const;
00024     inline void out_char(char c) const;
00025     int write(char const *s, unsigned long count,
00026              bool blocking = true) const override;
00027
00028 #ifndef UART_WITHOUT_INPUT
00029     int char_avail() const override;
00030     int get_char(bool blocking = true) const override;
00031 #endif
00032
00033 private:
00034     unsigned get_status() const;
00035 };
00036
00037 } // namespace L4

```

## 16.22 uart\_dm.h

```

00001 /*
00002  * Copyright (C) 2021-2022 Stephan Gerhold <stephan@gerhold.net>
00003  * Copyright (C) 2022-2025 Kernkonzept GmbH.
00004  * Author(s): Stephan Gerhold <stephan@gerhold.net>
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00008 #pragma once
00009
00010 #include "uart_base.h"
00011
00012 namespace L4 {
00013
00014 class Uart_dm : public Uart
00015 {
00016 public:
00017     explicit Uart_dm(unsigned /*base_rate*/) {}
00018     bool startup(Io_register_block const *) override;
00019     void shutdown() override;
00020     bool change_mode(Transfer_mode m, Baud_rate r) override;
00021     int tx_avail() const;
00022     void wait_tx_done() const;
00023     inline void out_char(char c) const;
00024     int write(char const *s, unsigned long count,
00025              bool blocking = true) const override;
00026
00027 #ifndef UART_WITHOUT_INPUT
00028     bool enable_rx_irq(bool enable = true) override;
00029     int char_avail() const override;
00030     int get_char(bool blocking = true) const override;
00031 #endif
00032 };
00033
00034 } // namespace L4

```

## 16.23 uart\_dummy.h

```

00001 /*
00002  * Copyright 2009 Technische Universität Dresden.
00003  * Copyright (C) 2023-2025 Kernkonzept GmbH.
00004  * Author(s): Adam Lackorzynski <adam@os.inf.tu-dresden.de>
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00008 #pragma once
00009
00010 #include "uart_base.h"
00011
00012 namespace L4 {

```

```

00013
00014 class Uart_dummy : public Uart
00015 {
00016 public:
00017     explicit Uart_dummy() {}
00018     explicit Uart_dummy(unsigned /*base_rate*/) {}
00019     bool startup(Io_register_block const *) override { return true; }
00020     void shutdown() override {}
00021     bool change_mode(Transfer_mode, Baud_rate) override { return true; }
00022     inline void out_char(char /*ch*/) const {}
00023     int write(char const * /*str*/, unsigned long /*count*/,
00024              bool /*blocking*/ = true) const override
00025     { return 0; }
00026
00027 #ifndef UART_WITHOUT_INPUT
00028     int char_avail() const override { return false; }
00029     int get_char(bool /*blocking*/ = true) const override { return 0; }
00030 #endif
00031 };
00032
00033 } // namespace L4

```

## 16.24 uart\_geni.h

```

00001 /*
00002  * Copyright (C) 2022-2025 Kernkonzept GmbH.
00003  * Author(s): Stephan Gerhold <stephan.gerhold@kernkonzept.com>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007 #pragma once
00008
00009 #include "uart_base.h"
00010
00011 namespace L4 {
00012
00013 class Uart_geni : public Uart
00014 {
00015 public:
00016     explicit Uart_geni(unsigned /*base_rate*/) {}
00017     bool startup(Io_register_block const *) override;
00018     void shutdown() override;
00019     bool change_mode(Transfer_mode m, Baud_rate r) override;
00020     int tx_avail() const;
00021     void wait_tx_done() const;
00022     void out_char(char c) const;
00023     int write(char const *s, unsigned long count,
00024             bool blocking = true) const override;
00025
00026 #ifndef UART_WITHOUT_INPUT
00027     bool enable_rx_irq(bool enable = true) override;
00028     void irq_ack() override;
00029     int char_avail() const override;
00030     int get_char(bool blocking = true) const override;
00031 #endif
00032 };
00033
00034 } // namespace L4

```

## 16.25 uart\_imx.h

```

00001 /*
00002  * Copyright (C) 2008-2009 Technische Universität Dresden.
00003  * Copyright (C) 2023-2025 Kernkonzept GmbH.
00004  * Author(s): Adam Lackorzynski <adam@os.inf.tu-dresden.de>
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00008 #pragma once
00009
00010 #include "uart_base.h"
00011
00012 namespace L4 {
00013
00014 class Uart_imx : public Uart
00015 {
00016 public:
00017     enum platform_type

```

```

00018 {
00019     Type_imx21,
00020     Type_imx35,
00021     Type_imx51,
00022     Type_imx6,
00023     Type_imx7,
00024     Type_imx8,
00025 };
00026 explicit Uart_imx(enum platform_type type) : _type(type) {}
00027 explicit Uart_imx(enum platform_type type, unsigned /*base_rate*/)
00028     : _type(type) {}
00029 bool startup(Io_register_block const *) override;
00030 void shutdown() override;
00031 bool change_mode(Transfer_mode m, Baud_rate r) override;
00032 int tx_avail() const;
00033 void wait_tx_done() const;
00034 inline void out_char(char c) const;
00035 int write(char const *s, unsigned long count,
00036           bool blocking = true) const override;
00037
00038 #ifndef UART_WITHOUT_INPUT
00039     bool enable_rx_irq(bool enable = true) override;
00040     int char_avail() const override;
00041     int get_char(bool blocking = true) const override;
00042 #endif
00043
00044 private:
00045     enum platform_type _type;
00046 };
00047
00048 class Uart_imx21 : public Uart_imx
00049 {
00050 public:
00051     Uart_imx21() : Uart_imx(Type_imx21) {}
00052     explicit Uart_imx21(unsigned base_rate) : Uart_imx(Type_imx21, base_rate) {}
00053 };
00054
00055 class Uart_imx35 : public Uart_imx
00056 {
00057 public:
00058     Uart_imx35() : Uart_imx(Type_imx35) {}
00059     explicit Uart_imx35(unsigned base_rate) : Uart_imx(Type_imx35, base_rate) {}
00060 };
00061
00062 class Uart_imx51 : public Uart_imx
00063 {
00064 public:
00065     Uart_imx51() : Uart_imx(Type_imx51) {}
00066     explicit Uart_imx51(unsigned base_rate) : Uart_imx(Type_imx51, base_rate) {}
00067 };
00068
00069 class Uart_imx6 : public Uart_imx
00070 {
00071 public:
00072     Uart_imx6() : Uart_imx(Type_imx6) {}
00073     explicit Uart_imx6(unsigned base_rate) : Uart_imx(Type_imx6, base_rate) {}
00074
00075 #ifndef UART_WITHOUT_INPUT
00076     void irq_ack() override;
00077 #endif
00078 };
00079
00080 class Uart_imx7 : public Uart_imx
00081 {
00082 public:
00083     Uart_imx7() : Uart_imx(Type_imx7) {}
00084     explicit Uart_imx7(unsigned base_rate) : Uart_imx(Type_imx7, base_rate) {}
00085 };
00086
00087 class Uart_imx8 : public Uart_imx
00088 {
00089 public:
00090     Uart_imx8() : Uart_imx(Type_imx8) {}
00091     explicit Uart_imx8(unsigned base_rate) : Uart_imx(Type_imx8, base_rate) {}
00092 };
00093
00094 } // namespace L4

```

## 16.26 uart\_leon3.h

```

00001 /*
00002  * Copyright (C) 2011 Technische Universität Dresden.
00003  * Copyright (C) 2023-2025 Kernkonzept GmbH.

```

```

00004  * Author(s): Adam Lackorzynski <adam@os.inf.tu-dresden.de>
00005  *           Björn Döbel <doebel@os.inf.tu-dresden.de>
00006  *
00007  * License: see LICENSE.spdx (in this directory or the directories above)
00008  */
00009 #pragma once
00010
00011 #include "uart_base.h"
00012
00013 namespace L4 {
00014
00015 class Uart_leon3 : public Uart
00016 {
00017 public:
00018     explicit Uart_leon3() {}
00019     explicit Uart_leon3(unsigned /*base_rate*/) {}
00020     bool startup(Io_register_block const *) override;
00021     void shutdown() override;
00022     bool change_mode(Transfer_mode m, Baud_rate r) override;
00023     int tx_avail() const;
00024     void wait_tx_done() const;
00025     inline void out_char(char c) const;
00026     int write(char const *s, unsigned long count,
00027              bool blocking = true) const override;
00028
00029 #ifndef UART_WITHOUT_INPUT
00030     bool enable_rx_irq(bool = true) override;
00031     int char_avail() const override;
00032     int get_char(bool blocking = true) const override;
00033 #endif
00034 };
00035
00036 } // namespace L4

```

## 16.27 uart\_linflex.h

```

00001 /*
00002  * Copyright (C) 2018 Technische Universität Dresden.
00003  * Copyright (C) 2023-2025 Kernkonzept GmbH.
00004  * Author(s): Adam Lackorzynski <adam@l4re.org>
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00008 #pragma once
00009
00010 #include "uart_base.h"
00011
00012 namespace L4 {
00013
00014 class Uart_linflex : public Uart
00015 {
00016 public:
00017     explicit Uart_linflex(unsigned) {}
00018     bool startup(Io_register_block const *) override;
00019     void shutdown() override;
00020     bool change_mode(Transfer_mode m, Baud_rate r) override;
00021     int tx_avail() const;
00022     void wait_tx_done() const;
00023     inline void out_char(char c) const;
00024     int write(char const *s, unsigned long count,
00025              bool blocking = true) const override;
00026
00027 #ifndef UART_WITHOUT_INPUT
00028     bool enable_rx_irq(bool enable = true) override;
00029     int char_avail() const override;
00030     int get_char(bool blocking = true) const override;
00031 #endif
00032
00033 private:
00034     void set_uartcr(bool fifo);
00035     bool is_tx_fifo_enabled() const;
00036     bool is_rx_fifo_enabled() const;
00037 };
00038
00039 } // namespace L4

```

## 16.28 uart\_lpuart.h

```

00001 /*

```



```

00002  * Copyright (C) 2019, 2023-2025 Kernkonzept GmbH.
00003  * Author(s): Adam Lackorzynski <adam@l4re.org>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007 #pragma once
00008
00009 #include "uart_base.h"
00010
00011 namespace L4 {
00012
00013 class Uart_lpuart : public Uart
00014 {
00015 public:
00017     Uart_lpuart(unsigned freq = 0) : _freq(freq) {}
00018     bool startup(Io_register_block const *) override;
00019     void shutdown() override;
00020     bool change_mode(Transfer_mode m, Baud_rate r) override;
00021     int tx_avail() const;
00022     void wait_tx_done() const {}
00023     inline void out_char(char c) const;
00024     int write(char const *s, unsigned long count,
00025               bool blocking = true) const override;
00026
00027 #ifndef UART_WITHOUT_INPUT
00028     bool enable_rx_irq(bool enable = true) override;
00029     int char_avail() const override;
00030     int get_char(bool blocking = true) const override;
00031 #endif
00032
00033 private:
00034     unsigned _freq;
00035 };
00036
00037 } // namespace L4

```

## 16.29 uart\_mvebu.h

```

00001 /*
00002  * Copyright (C) 2017, 2023-2025 Kernkonzept GmbH.
00003  * Author(s) Adam Lackorzynski <adam@l4re.org>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007 #pragma once
00008
00009 #include "uart_base.h"
00010
00011 namespace L4 {
00012
00013 class Uart_mvebu : public Uart
00014 {
00015 public:
00016     explicit Uart_mvebu(unsigned baserate) : _baserate(baserate) {}
00017     bool startup(Io_register_block const *) override;
00018     void shutdown() override;
00019     bool change_mode(Transfer_mode m, Baud_rate r) override;
00020     int tx_avail() const;
00021     void wait_tx_done() const {}
00022     inline void out_char(char c) const;
00023     int write(char const *s, unsigned long count,
00024               bool blocking = true) const override;
00025
00026 #ifndef UART_WITHOUT_INPUT
00027     bool enable_rx_irq(bool enable = true) override;
00028     int char_avail() const override;
00029     int get_char(bool blocking = true) const override;
00030 #endif
00031
00032 private:
00033     unsigned _baserate;
00034 };
00035
00036 } // namespace L4

```

## 16.30 uart\_of.h

```

00001 /*

```

```

00002  * Copyright (C) 2009 Technische Universität Dresden.
00003  * Copyright (C) 2023-2025 Kernkonzept GmbH.
00004  * Author(s): Adam Lackorzynski <adam@os.inf.tu-dresden.de>
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00008 #pragma once
00009
00010 #include "uart_base.h"
00011 #include <stdarg.h>
00012 #include <string.h>
00013 #include <l4/drivers/of.h>
00014
00015 namespace L4 {
00016
00017 class Uart_of : public Uart, public L4_drivers::Of
00018 {
00019 private:
00020     ihandle_t _serial;
00021
00022 public:
00023     Uart_of() : Of(), _serial(0) {}
00024     explicit Uart_of(unsigned /*base_rate*/) : Of(), _serial(0) {}
00025     bool startup(Io_register_block const *) override;
00026     void shutdown() override;
00027     bool change_mode(Transfer_mode m, Baud_rate r) override;
00028     int tx_avail() const;
00029     void out_char(char c) const;
00030     int write(char const *s, unsigned long count,
00031              bool blocking = true) const override;
00032
00033 #ifndef UART_WITHOUT_INPUT
00034     int char_avail() const override;
00035     int get_char(bool blocking = true) const override;
00036 #endif
00037 };
00038
00039 } // namespace L4

```

## 16.31 uart\_omap35x.h

```

00001 /*
00002  * Copyright (C) 2009 Technische Universität Dresden.
00003  * Copyright (C) 2023-2025 Kernkonzept GmbH.
00004  * Author(s): Adam Lackorzynski <adam@os.inf.tu-dresden.de>
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00008 #pragma once
00009
00010 #include "uart_base.h"
00011
00012 namespace L4 {
00013
00014 class Uart_omap35x : public Uart
00015 {
00016 public:
00017     explicit Uart_omap35x() {}
00018     explicit Uart_omap35x(unsigned /*base_rate*/) {}
00019     bool startup(Io_register_block const *) override;
00020     void shutdown() override;
00021     bool change_mode(Transfer_mode m, Baud_rate r) override;
00022     int tx_avail() const;
00023     void wait_tx_done() const;
00024     inline void out_char(char c) const;
00025     int write(char const *s, unsigned long count,
00026              bool blocking = true) const override;
00027
00028 #ifndef UART_WITHOUT_INPUT
00029     bool enable_rx_irq(bool) override;
00030     int char_avail() const override;
00031     int get_char(bool blocking = true) const override;
00032 #endif
00033 };
00034
00035 } // namespace L4

```

## 16.32 uart\_pl011.h

```

00001 /*

```

```

00002  * Copyright (C) 2009 Technische Universität Dresden.
00003  * Copyright (C) 2023-2025 Kernkonzept GmbH.
00004  * Author(s): Adam Lackorzynski <adam@os.inf.tu-dresden.de>
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00008 #pragma once
00009
00010 #include "uart_base.h"
00011
00012 namespace L4 {
00013
00014 class Uart_pl011 : public Uart
00015 {
00016 public:
00017     Uart_pl011(unsigned freq) : _freq(freq) {}
00018     bool startup(Io_register_block const *) override;
00019     void shutdown() override;
00020     bool change_mode(Transfer_mode m, Baud_rate r) override;
00021     int tx_avail() const;
00022     void wait_tx_done() const;
00023     inline void out_char(char c) const;
00024     int write(char const *s, unsigned long count,
00025              bool blocking = true) const override;
00026
00027 #ifndef UART_WITHOUT_INPUT
00028     bool enable_rx_irq(bool enable) override;
00029     int char_avail() const override;
00030     int get_char(bool blocking = true) const override;
00031 #endif
00032 private:
00033     void set_rate(Baud_rate r);
00034     unsigned _freq;
00035 };
00036
00037 } // namespace L4

```

## 16.33 uart\_s3c2410.h

```

00001 /*
00002  * Copyright (C) 2009-2012 Technische Universität Dresden.
00003  * Copyright (C) 2023-2025 Kernkonzept GmbH.
00004  * Author(s): Adam Lackorzynski <adam@os.inf.tu-dresden.de>
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00008 #pragma once
00009
00010 #include "uart_base.h"
00011
00012 namespace L4 {
00013
00014 class Uart_s3c : public Uart
00015 {
00016 protected:
00017     enum Uart_type
00018     {
00019         Type_24xx, Type_64xx, Type_s5pv210,
00020     };
00021
00022     Uart_type type() const { return _type; }
00023
00024 public:
00025     explicit Uart_s3c(Uart_type type) : _type(type) {}
00026     explicit Uart_s3c(Uart_type type, unsigned /*base_rate*/) : _type(type) {}
00027     bool startup(Io_register_block const *) override;
00028     void shutdown() override;
00029     bool change_mode(Transfer_mode m, Baud_rate r) override;
00030     int tx_avail() const;
00031     void wait_tx_done() const;
00032     inline void out_char(char c) const;
00033     int write(char const *s, unsigned long count,
00034              bool blocking = true) const override;
00035     void fifo_reset();
00036
00037 #ifndef UART_WITHOUT_INPUT
00038     int char_avail() const override;
00039     int get_char(bool blocking = true) const override;
00040 #endif
00041
00042 protected:
00043     virtual void ack_rx_irq() const = 0;

```

```

00044     virtual void wait_for_empty_tx_fifo() const = 0;
00045     virtual unsigned is_rx_fifo_non_empty() const = 0;
00046     virtual unsigned is_tx_fifo_not_full() const = 0;
00047
00048 private:
00049     Uart_type _type;
00050 };
00051
00052 class Uart_s3c2410 : public Uart_s3c
00053 {
00054 public:
00055     Uart_s3c2410() : Uart_s3c(Type_24xx) {}
00056     explicit Uart_s3c2410(unsigned base_rate) : Uart_s3c(Type_24xx, base_rate) {}
00057
00058 protected:
00059     void ack_rx_irq() const override {}
00060     void wait_for_empty_tx_fifo() const override;
00061     unsigned is_rx_fifo_non_empty() const override;
00062     unsigned is_tx_fifo_not_full() const override;
00063
00064     void auto_flow_control(bool on);
00065 };
00066
00067 class Uart_s3c64xx : public Uart_s3c
00068 {
00069 public:
00070     Uart_s3c64xx() : Uart_s3c(Type_64xx) {}
00071     explicit Uart_s3c64xx(unsigned base_rate) : Uart_s3c(Type_64xx, base_rate) {}
00072
00073 protected:
00074     void ack_rx_irq() const override;
00075     void wait_for_empty_tx_fifo() const override;
00076     unsigned is_rx_fifo_non_empty() const override;
00077     unsigned is_tx_fifo_not_full() const override;
00078 };
00079
00080 class Uart_s5pv210 : public Uart_s3c
00081 {
00082 public:
00083     Uart_s5pv210() : Uart_s3c(Type_s5pv210) {}
00084     explicit Uart_s5pv210(unsigned base_rate) : Uart_s3c(Type_s5pv210, base_rate) {}
00085
00086 protected:
00087     void ack_rx_irq() const override;
00088     void wait_for_empty_tx_fifo() const override;
00089     unsigned is_rx_fifo_non_empty() const override;
00090     unsigned is_tx_fifo_not_full() const override;
00091 };
00092
00093 } // namespace L4

```

## 16.34 uart\_sa1000.h

```

00001 /*
00002  * Copyright (C) 2008-2012 Technische Universität Dresden.
00003  * Copyright (C) 2023-2025 Kernkonzept GmbH.
00004  * Author(s): Adam Lackorzynski <adam@os.inf.tu-dresden.de>
00005  *            Alexander Warg <alexander.warg@os.inf.tu-dresden.de>
00006  *
00007  * License: see LICENSE.spdx (in this directory or the directories above)
00008  */
00009 #pragma once
00010
00011 #include "uart_base.h"
00012
00013 namespace L4 {
00014
00015 class Uart_sa1000 : public Uart
00016 {
00017 public:
00018     explicit Uart_sa1000() {}
00019     explicit Uart_sa1000(unsigned /*base_rate*/) {}
00020     bool startup(Io_register_block const *) override;
00021     void shutdown() override;
00022     bool change_mode(Transfer_mode m, Baud_rate r) override;
00023     int tx_avail() const;
00024     void wait_tx_done() const;
00025     inline void out_char(char c) const;
00026     int write(char const *s, unsigned long count,
00027              bool blocking = true) const override;
00028
00029 #ifndef UART_WITHOUT_INPUT
00030     int char_avail() const override;

```

```

00031 int get_char(bool blocking = true) const override;
00032 #endif
00033 };
00034
00035 } // namespace L4

```

## 16.35 uart\_sbi.h

```

00001 /*
00002  * Copyright (C) 2021, 2024-2025 Kernkonzept GmbH.
00003  * Author(s): Georg Kotheimer <georg.kotheimer@kernkonzept.com>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007 #pragma once
00008
00009 #include "uart_base.h"
00010
00011 namespace L4 {
00012
00013 class Uart_sbi : public Uart
00014 {
00015 public:
00016     Uart_sbi();
00017     explicit Uart_sbi(unsigned /*base_rate*/) : Uart_sbi() {}
00018     bool startup(Io_register_block const *) override;
00019     void shutdown() override;
00020     bool change_mode(Transfer_mode m, Baud_rate r) override;
00021     int tx_avail() const { return true; }
00022     void wait_tx_done() const {}
00023     inline void out_char(char c) const;
00024     int write(char const *s, unsigned long count,
00025              bool blocking = true) const override;
00026
00027 #ifndef UART_WITHOUT_INPUT
00028     int char_avail() const override;
00029     int get_char(bool blocking = true) const override;
00030 #endif
00031
00032 private:
00033     mutable int _bufchar;
00034 };
00035
00036 } // namespace L4

```

## 16.36 uart\_sh.h

```

00001 /*
00002  * Copyright (C) 2016 Technische Universität Dresden.
00003  * Copyright (C) 2023-2025 Kernkonzept GmbH.
00004  * Author(s): Adam Lackorzynski <adam@l4re.org>
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00008 #pragma once
00009
00010 #include "uart_base.h"
00011
00012 namespace L4 {
00013
00014 class Uart_sh : public Uart
00015 {
00016 public:
00017     explicit Uart_sh() {}
00018     explicit Uart_sh(unsigned /*base_rate*/) {}
00019     bool startup(Io_register_block const *) override;
00020     void shutdown() override;
00021     bool change_mode(Transfer_mode m, Baud_rate r) override;
00022     int tx_avail() const;
00023     void wait_tx_done() const {}
00024     inline void out_char(char c) const;
00025     int write(char const *s, unsigned long count,
00026              bool blocking = true) const override;
00027
00028 #ifndef UART_WITHOUT_INPUT
00029     bool enable_rx_irq(bool enable = true) override;
00030     void irq_ack() override;
00031     int char_avail() const override;

```

```

00032     int get_char(bool blocking = true) const override;
00033 #endif
00034 };
00035
00036 } // namespace L4

```

## 16.37 uart\_sifive.h

```

00001 /*
00002  * Copyright (C) 2021-2025 Kernkonzept GmbH.
00003  * Author(s): Georg Kotheimer <georg.kotheimer@kernkonzept.com>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007 #pragma once
00008
00009 #include "uart_base.h"
00010
00011 namespace L4 {
00012
00013     class Uart_sifive : public Uart
00014     {
00015     public:
00016         Uart_sifive(unsigned freq) : _freq(freq), _bufchar(-1) {}
00017         bool startup(Io_register_block const *) override;
00018         void shutdown() override;
00019         bool change_mode(Transfer_mode m, Baud_rate r) override;
00020         int tx_avail() const;
00021         void wait_tx_done() const;
00022         inline void out_char(char c) const;
00023         int write(char const *s, unsigned long count,
00024                 bool blocking = true) const override;
00025
00026 #ifndef UART_WITHOUT_INPUT
00027         bool enable_rx_irq(bool enable) override;
00028         int char_avail() const override;
00029         int get_char(bool blocking = true) const override;
00030 #endif
00031
00032     private:
00033         unsigned _freq;
00034         mutable int _bufchar;
00035     };
00036
00037 } // namespace L4

```

## 16.38 uart\_tegra-tcu.h

```

00001 /*
00002  * Copyright (C) 2025 Kernkonzept GmbH.
00003  * Author(s): Adam Lackorzynski <adam@l4re.org>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007 #pragma once
00008
00009 #include "uart_base.h"
00010
00011 namespace L4 {
00012
00013     class Uart_tegra_tcu : public Uart
00014     {
00015     public:
00016         Uart_tegra_tcu() {}
00017         Uart_tegra_tcu(unsigned long) {}
00018         bool startup(Io_register_block const *tx_mbox) override;
00019         void set_rx_mbox(Io_register_block const *rx_mbox);
00020         void shutdown() override;
00021         bool change_mode(Transfer_mode m, Baud_rate r) override;
00022         int tx_avail() const;
00023         void wait_tx_done() const {}
00024         inline void out_char(char c) const;
00025         int write(char const *s, unsigned long count,
00026                 bool blocking = true) const override;
00027
00028 #ifndef UART_WITHOUT_INPUT
00029         int char_avail() const override;
00030         int get_char(bool blocking = true) const override;
00031 #endif
00032     };
00033
00034 } // namespace L4

```

```

00031 #endif
00032
00033 private:
00034     mutable unsigned _current_rx_val = 0u;
00035     Io_register_block const *_rx_mbox = nullptr;
00036 };
00037
00038 } // namespace L4

```

## 16.39 tutorial.lua

```

00001 local _doc = [=[
00002
00003 Tutorial lua script for Ned
00004 =====
00005
00006 Firstly we have a set of definitions available. Some come from 'ned.lua'
00007 embedded script and others from the C++ bindings within Ned. The whole L4
00008 functionality is in the lua module "L4" (use 'local L4 = require("L4");').
00009 The L4 module classes and functions cope with L4 capabilities and
00010 their invocations, provide a set of constants and access to the L4Re environment of
00011 the running program. Finally, of course it can also start L4 applications.
00012
00013 L4 Capabilities
00014 =====
00015
00016 The L4 module defines a user data type for capabilities. A capability in lua
00017 carries a typed L4 capability and is accompanied with a set of type specific
00018 methods that may be called on the object behind the capability. There also
00019 exists a way to cast a capability to a capability to a different type of
00020 object using L4.cast(type, cap).
00021
00022 L4.cast(type, cap)
00023
00024 Returns a cap transformed to a capability of the given type, whereas type
00025 is either the fully qualified C++ name of the class encapsulating the object
00026 or the L4 protocol ID assigned to all L4Re and L4 system objects.
00027 If the type is unknown then nil is returned.
00028
00029 Generic capabilities provide the following methods:
00030
00031 is_valid()
00032
00033 Returns true if the capability is not the invalid cap (L4_INVALID_CAP), and
00034 false if it is the invalid cap.
00035
00036
00037 L4Re::Namespace object
00038 =====
00039
00040 There is a lua type for name spaces that has the following methods:
00041
00042 query(name), or q(name)
00043
00044 Returns a closure (function) that initiates a query for the given name
00045 within the name space. The function takes no arguments and returns
00046 a capability if successful or nil if name is not found.
00047
00048
00049 link(name), or l(name)
00050
00051 Returns a function that can create a link to the given object in the name
00052 space if put into another name space. The function takes two parameters
00053 the target name space and the name in the target name space.
00054 Loader:create_namespace and Loader.fill_namespace calls this function
00055 when things are really put into an L4Re::Namespace.
00056
00057
00058 register(name, cap), or r(name, cap)
00059
00060 Registers the given object capability under the given name. cap can
00061 be either a real capability (note query returns a function), a string, or
00062 nil. If it is a capability it is just put into the name space.
00063 In the case cap is a string a placeholder will be put into the name space
00064 that will be replaced with a real capability later by some program.
00065 And if nil is use the name will be deleted from the name space.
00066
00067
00068 L4::Factory object
00069 =====
00070
00071 The factory object provides an interface to the generic create method of a
00072 factory.

```

```

00073
00074 create(proto, ...)
00075
00076 This method calls the factory to create an object of the given type,
00077 via the L4 protocol number (see L4.Proto table for more) all further
00078 arguments are passed to the factory.
00079
00080
00081 Access to the L4Re Env capabilities
00082 =====
00083
00084 The L4 module defines a table L4.Env that contains the capabilities
00085 of the L4Re::Env::env() environment. Namely:
00086
00087 factory      The kernel factory of Ned
00088 log           The log object of Ned
00089 user_factory  The factory provided to Ned, including memory
00090 parent        The parent of Ned
00091 rm            The region map of Ned
00092 scheduler     The scheduler of Ned
00093
00094
00095 Some useful constants
00096 =====
00097
00098 L4.Proto table contains the most important protocol values for
00099 L4 and L4Re objects.
00100
00101 Namespace
00102 Goos
00103 Rm
00104 Irq
00105 Sigma0
00106 Factory
00107 Log
00108 Scheduler
00109
00110 The L4.Info table contains the following functions:
00111
00112 Kip.str()     The banner string found in the kernel info page
00113 arch()        Architecture name, such as: x86, amd64, arm, ppc32
00114 platform()    Platform name, such as: pc, ux, realview, beagleboard
00115 mword_bits() Number of native machine word bits (32, 64)
00116
00117
00118 Support for starting L4 programs
00119 =====
00120
00121 The L4 module defines two classes that are useful for starting L4 applications.
00122 The class L4.Loader that encapsulates a fairly high level policy
00123 that is useful for starting a whole set of processes. And the class L4.App_env
00124 that encapsulates a more fine-grained policy.
00125
00126 L4.Loader
00127 -----
00128
00129 The class L4.Loader encapsulates the policy for starting programs with the
00130 basic building blocks for the application coming from a dedicated loader,
00131 such as Moe or a Loader instance. These building blocks are a region map (Rm),
00132 a scheduler, a memory allocator, and a logging facility.
00133 A L4.Loader object is typically used to start multiple applications. There
00134 is a L4.default_loader instance of L4.Loader that uses the L4.Env.mem_alloc
00135 factory of the current Ned instance to create the objects for a new program.
00136 However you may also use a more restricted factory for applications and
00137 instantiate a loader for them. The L4.Loader objects can already be used
00138 to start a program with L4.Loader:start(app_spec, cmd, ...). Where app_spec
00139 is a table containing parameters for the new application. cmd is the
00140 command to run and the remaining arguments are the command-line options for
00141 the application.
00142
00143 ]==]
00144
00145 L4.default_loader:start({}, "rom/hello");
00146
00147 local _doc = [=[
00148
00149 This statement does the following:
00150 1. Create a new environment for the application
00151 2. Add the rom name-space into the new environment (thus shares Ned's
00152    'rom' directory with the new program).
00153 3. Creates all the building blocks for the new process and starts the
00154    'l4re' support kernel in the new process which in turn starts 'rom/hello'
00155    in the new process.
00156
00157 Using the app_spec parameter you can modify the behavior in two ways. There are
00158 two supported options 'caps' for providing more capabilities for the
00159 application. And 'log' for modifying the logger tag and color.

```



```

00160
00161 ]==]
00162
00163 local my_caps = {
00164     fb = L4.Env.vesa;
00165 };
00166
00167 L4.default_loader:start({caps = my_caps, log = {"APP", "blue"}}, "rom/hello");
00168
00169 local _doc = [=[
00170
00171 This snippet creates a caps template (my_caps) and uses it for the
00172 new process and also sets user-defined log tags. The L4.Loader:start method,
00173 however, automatically adds the 'rom' directory to the caps environment if
00174 not already specified in the template.
00175
00176 Environment variables may be given as a table in the third argument to
00177 start. Argument to the program are given space separated after the program
00178 name within a single string.
00179
00180 ]==]
00181
00182 L4.default_loader:start({}, "rom/program arg1 " .. arg2, { LD_DEBUG = 1 });
00183
00184 local _doc = [=[
00185
00186 L4.default_loader:startv is a variant of the start function that takes the
00187 arguments of the program as a single argument each. If the last argument to
00188 startv is a table it is interpreted as environment variables for the program.
00189 The above example would translate to:
00190
00191 ]==]
00192
00193 L4.default_loader:startv({}, "rom/program", "arg1", arg2, { LD_DEBUG = 1 });
00194
00195 local _doc = [=[
00196
00197 To create a new L4.Loader instance you may use a generic factory for all
00198 building blocks or set individual factories.
00199
00200 ]==]
00201
00202 l = L4.Loader.new({
00203     mem = L4.Env.user_factory:create(L4.Proto.Factory, 512*1024):m("rs")
00204 });
00205
00206 local _doc = [=[
00207
00208 Creates a loader instance that uses the newly created 512 KB factory for
00209 all building blocks. To set individual factories use the options:
00210 'mem'          as memory allocator for the new processes and as
00211                default factory for all objects not explicitly set to a
00212                different factory
00213 'log_fab'      for creating log objects.
00214 'ns_fab'       for creating name-space objects.
00215 'rm_fab'       for creating region-map objects.
00216
00217
00218
00219 L4.App_env
00220 -----
00221
00222 L4.App_env provides a more fine-grained control for a single process or for a
00223 limited number of processes. L4.App_env uses an L4.Loader object as basic
00224 facility. However you can override the memory allocator 'mem' for the new
00225 process as well as the kernel factory 'factory', the log capability etc.
00226
00227 ]==]
00228
00229 local e = L4.App_env.new({
00230     loader = l,
00231     mem = L4.Env.user_factory:create(L4.Proto.Factory, 128*1024):m("rs")
00232 });
00233
00234 e:start("rom/hello");

```

## 16.40 cmd\_control

```

00001 // -*- Mode: C++ -*-
00002 // vim:ft=cpp
00003 /*
00004  * Copyright (C) 2016, 2024 Kernkonzept GmbH.
00005  * Author(s): Sarah Hoffmann <sarah.hoffmann@kernkonzept.com>

```

```

00006  *
00007  * License: see LICENSE.spdx (in this directory or the directories above)
00008  */
00009 #pragma once
00010
00011 #include <l4/sys/cxx/ipc_epiface>
00012 #include <l4/sys/cxx/ipc_string>
00013
00014 namespace L4Re { namespace Ned {
00015
00016     class Cmd_control : public L4::Kobject_0t<Cmd_control>
00017     {
00018     public:
00019         L4_INLINE_RPC_NF(long, execute, (L4::Ipc::String<> cmd,
00020                                         L4::Ipc::Array<char> &result));
00021
00022     public:
00023         long execute(L4::Ipc::String<> cmd) noexcept
00024         {
00025             L4::Ipc::Array<char> res(0, NULL);
00026             return execute_t::call(c(), cmd, res);
00027         }
00028
00029         long execute(L4::Ipc::String<> cmd,
00030                     L4::Ipc::String<char> *result) noexcept
00031         {
00032             L4::Ipc::Array<char> res(result->length, result->data);
00033             long r = execute_t::call(c(), cmd, res);
00034             if (r >= 0)
00035                 result->length = res.length;
00036             return r;
00037         }
00038
00039         typedef L4::Typeid::Rpc<execute_t> Rpc;
00040     };
00041 } } // namespace

```

## 16.41 pkg/uvmm/configs/vmm.lua File Reference

### Functions

- [new\\_sched](#) ( prio, cpu\_mask, ...)
- [start\\_io](#) ( busses, cmdline, opts)
- [set\\_sched](#) ( opts, prio, cpus, ...)
- [start\\_virtio\\_switch](#) ( ports, prio, cpus, switch\_type, ext\_caps)
- [start\\_virtio\\_switch\\_tbl](#) ( options)
- [start\\_vm](#) ( options)

### 16.41.1 Function Documentation

#### 16.41.1.1 new\_sched()

```

new_sched (
    prio,
    cpu_mask,
    ... )

```

Creates a new scheduler proxy at moe.

#### Parameters

<i>prio</i>	Base priority of the threads running in the scheduler proxy
-------------	---

<i>cpu_mask</i>	First of a list of CPU masks for the first 64 CPUs to use for the scheduler proxy
...	more CPU masks

**Returns**

created scheduler

**16.41.1.2 set\_sched()**

```
set_sched (
    opts,
    prio,
    cpus,
    ... )
```

Create scheduler proxy and add it into the *opts* table under the key *scheduler*.

**Parameters**

<i>in, out</i>	<i>opts</i>	option table
	<i>prio</i>	thread priority (or <i>nil</i> )
	<i>cpus</i>	cpu mask (or <i>nil</i> )
	...	more CPU masks

There are four possibilities for values of *prio* and *cpus*:

- No *prio* and no *cpus*: No scheduler proxy created.
- A *prio*, but no *cpus*: Create a scheduler proxy with only a priority limit.
- No *Prio*, but *cpus*: Create a scheduler proxy with default *prio* and *cpus* limit.
- A *prio* and *cpus*: Create a scheduler proxy with given limits.

**16.41.1.3 start\_io()**

```
start_io (
    busses,
    cmdline,
    opts)
```

Start IO service with the given options

**Parameters**

<i>in, out</i>	<i>busses</i>	table of vBus names as keys. Uses io config <i>&lt;name&gt;.vbus</i> to fill vBus <i>&lt;name&gt;</i> .
----------------	---------------	---

	<i>cmdline</i>	io command line parameters
	<i>opts</i>	Option table for loader.start function, e.g. scheduler or ext_caps. Entries from ext_caps have precedence over default caps created by this function.

After this function returns the created vBusses are located in the table passed as *busses*.

#### 16.41.1.4 start\_virtio\_switch()

```
start_virtio_switch (
    ports,
    prio,
    cpus,
    switch_type,
    ext_caps)
```

Start virtio network application.

**Deprecated** This function exists for backwards compatibility reasons and calls [start\\_virtio\\_switch\\_tbl](#) with an appropriate *options* table

#### Parameters

<i>in, out</i>	<i>ports</i>	table with port names as keys
	<i>prio</i>	priority for started thread
	<i>cpus</i>	cpu mask for started thread
	<i>switch_type</i>	Selects application to start. Either <i>switch</i> or <i>p2p</i>
	<i>ext_caps</i>	Extra capabilities to pass to the started application

The *switch\_type* *switch* can take additional arguments to create a port at the switch. To pass these arguments for a specific port, pass a table as value for a key in the *ports* table.

#### 16.41.1.5 start\_virtio\_switch\_tbl()

```
start_virtio_switch_tbl (
    options)
```

Start virtio network application.

#### Parameters

<i>options</i>	A table of parameters
----------------	-----------------------

The following keys are supported in the *options* table:

table key	value
ports	table with port names as keys
scheduler	scheduler (e.g. created with new_sched)
switch_type	selects application to start. Either <code>switch</code> or <code>p2p</code>
ext_caps	Extra capabilities to pass to the started application
svr_cap	cap slot to be used for the server interface
port_limit	the maximum number of dynamic ports the switch shall support

The `switch_type` `switch` can take additional arguments to create a port at the switch. To pass these arguments for a specific port, pass a table as value for a key in the `ports` table.

#### Note

The `svr_cap` capability requires server rights, use `":svr()"`.

### 16.41.1.6 start\_vm()

```
start_vm (
    options)
```

Start UVMM

#### Parameters

<i>options</i>	A table of parameters
----------------	-----------------------

The following keys are supported in the `options` table:

table key	value
bootargs	command line for guest kernel
cpus	cpu mask
ext_args	additional arguments to pass to UVMM
fdt	file name of the device tree
id	an integer identifying the VM
jdb	jdb capability
kernel	file name of the guest kernel binary
mem	RAM size in MiB <i>or</i> dataspace cap for guest memory.
mem_align	alignment for the guest memory in bits. Ignored if <code>mem</code> is a cap.
mon	monitor application file name
net	a virtio cap, e.g. for network
prio	thread priority
ram_base	start of guest memory
rd	file name of the ramdisk

table key	value
scheduler	a scheduler cap. If used, prio and cpus are ignored.
vbus	the vBus to attach to the VM

## 16.42 vmm.lua

[Go to the documentation of this file.](#)

```

00001 --! \file vmm.lua
00002
00003 local L4 = require "L4";
00004
00005 local l = L4.Loader.new({mem = L4.Env.user_factory});
00006 loader = l;
00007
00008 --[[!
00009 \internal
00010
00011 Utility function to merge several lua tables
00012
00013 \param ... one or more tables
00014
00015 \note Later tables are given more priority when merging
00016
00017 \return a new combined table
00018 ]]
00019 function table_override(...)
00020     local combined = {}
00021     for _, tab in ipairs({...}) do
00022         for k, v in pairs(tab) do
00023             combined[k] = v
00024         end
00025     end
00026     return combined
00027 end
00028
00029 --[[!
00030 Creates a new scheduler proxy at moe.
00031
00032 \param prio      Base priority of the threads running in the scheduler proxy
00033 \param cpu_mask  First of a list of CPU masks for the first 64 CPUs to use for
00034                  the scheduler proxy
00035 \param ...       more CPU masks
00036
00037 \return created scheduler
00038 ]]
00039 function new_sched(prio, cpu_mask, ...)
00040     return L4.Env.user_factory:create(L4.Proto.Scheduler, prio + 10, prio,
00041                                       cpu_mask, ...);
00042 end
00043
00044 --[[!
00045 Start IO service with the given options
00046
00047 \param[in,out] busses  table of vBus names as keys. Uses io config
00048                       `

```

```

00073 };
00074
00075 local files = "";
00076
00077 for k, v in pairs(busses) do
00078     if caps[k] ~= nil then
00079         print("Warning: overwriting caps." .. k .. " with vbus of same name.")
00080     end
00081     local c = l:new_channel();
00082     busses[k] = c
00083     caps[k] = c:svr();
00084     files = files .. " rom/" .. k .. ".vbus";
00085 end
00086
00087 opts.caps = table_override(caps, opts.caps or {}, opts.ext_caps or {})
00088 opts.log = opts.log or { "io", "red" }
00089
00090 return l:start(opts, "rom/io " .. cmdline .. files)
00091 end
00092
00093 --[[
00094 Create scheduler proxy and add it into the `opts` table under
00095 the key `scheduler`.
00096
00097 \param[in,out] opts option table
00098 \param prio thread priority (or `nil`)
00099 \param cpus cpu mask (or `nil`)
00100 \param ... more CPU masks
00101
00102 There are four possibilities for values of prio and cpus:
00103
00104 \li No prio and no cpus: No scheduler proxy created.
00105 \li A prio, but no cpus: Create a scheduler proxy with only a priority limit.
00106 \li No Prio, but cpus: Create a scheduler proxy with default prio and cpus
00107     limit.
00108 \li A prio and cpus: Create a scheduler proxy with given limits.
00109 ]]
00110 function set_sched(opts, prio, cpus, ...)
00111     if cpus == nil and prio == nil then
00112         return
00113     end
00114
00115     if prio == nil then
00116         -- Default to zero to use the L4Re Default_thread_prio
00117         prio = 0
00118     end
00119
00120     local sched = new_sched(prio, cpus, ...);
00121     opts["scheduler"] = sched;
00122 end
00123
00124 --[[
00125 Start virtio network application.
00126
00127 \deprecated This function exists for backwards compatibility reasons and calls
00128 \ref start_virtio_switch_tbl with an appropriate `options` table
00129
00130 \param[in,out] ports table with port names as keys
00131 \param prio priority for started thread
00132 \param cpus cpu mask for started thread
00133 \param switch_type Selects application to start. Either `switch` or `p2p`
00134 \param ext_caps Extra capabilities to pass to the started application
00135
00136 The switch_type `switch` can take additional arguments to create a port at the
00137 switch. To pass these arguments for a specific port, pass a table as value for
00138 a key in the ports table.
00139
00140 ]]
00141 function start_virtio_switch(ports, prio, cpus, switch_type, ext_caps)
00142     local opts = {
00143         ports = ports,
00144         switch_type = switch_type,
00145         ext_caps = ext_caps,
00146     }
00147     set_sched(opts, prio, cpus)
00148     return start_virtio_switch_tbl(opts)
00149 end
00150
00151 --[[
00152 Start virtio network application.
00153
00154 \param options A table of parameters
00155
00156 The following keys are supported in the `options` table:
00157
00158 | table key | value |
00159 | ----- | ----- |

```

```

00160 | `ports`      | table with port names as keys |
00161 | `scheduler`  | scheduler (e.g. created with new_sched) |
00162 | `switch_type`| selects application to start. Either `switch` or `p2p` |
00163 | `ext_caps`   | Extra capabilities to pass to the started application |
00164 | `svr_cap`    | cap slot to be used for the server interface |
00165 | `port_limit` | the maximum number of dynamic ports the switch shall support |
00166
00167 The switch_type `switch` can take additional arguments to create a port at the
00168 switch. To pass these arguments for a specific port, pass a table as value for
00169 a key in the ports table.
00170
00171 \note The `svr_cap` capability requires server rights, use ":svr()".
00172 ]]
00173 function start_virtio_switch_tbl(options)
00174     local ports = options.ports;
00175     local scheduler = options.scheduler;
00176     local switch_type = options.switch_type;
00177     local ext_caps = options.ext_caps;
00178     local svr_cap = options.svr_cap;
00179     local port_limit = options.port_limit;
00180
00181     if svr_cap and port_limit == nil then
00182         print("Warning: start_virtio_switch_tbl(): `svr_cap` defined, but no "..
00183             "'port_limit' set. The svr_cap will not support dynamic port "..
00184             "creation.")
00185     end
00186
00187     if port_limit and svr_cap == nil then
00188         error("start_virtio_switch_tbl(): `port_limit` set, but no `svr_cap`. "..
00189             "This is not supported")
00190     end
00191
00192     local switch
00193
00194     if svr_cap then
00195         switch = svr_cap:svr()
00196     else
00197         switch = l:new_channel()
00198     end
00199
00200     local opts = {
00201         log = { "switch", "Blue" },
00202         caps = table_override({ svr = switch:svr() }, ext_caps or {});
00203     };
00204
00205     if scheduler then
00206         opts["scheduler"] = scheduler;
00207     end
00208
00209     if switch_type == "switch" then
00210         local port_count = 0;
00211         for k, v in pairs(ports) do
00212             port_count = port_count + 1;
00213         end
00214         if port_limit then
00215             port_count = port_count + port_limit
00216         end
00217
00218         svr = l:start(opts, "rom/l4vio_switch -v -p " .. port_count );
00219
00220         for k, extra_opts in pairs(ports) do
00221             if type(extra_opts) ~= "table" then
00222                 extra_opts = {}
00223             end
00224
00225             ports[k] = L4.cast(L4.Proto.Factory, switch):create(
00226                 0,
00227                 "ds-max=4",
00228                 "name=" .. k,
00229                 table.unpack(extra_opts)
00230             )
00231         end
00232     else
00233         svr = l:start(opts, "rom/l4vio_net_p2p");
00234
00235         for k, v in pairs(ports) do
00236             ports[k] = L4.cast(L4.Proto.Factory, switch):create(0, "ds-max=4");
00237         end
00238     end
00239
00240     return svr;
00241 end
00242
00243 --[[!
00244 Start UVMM
00245
00246 \param options A table of parameters

```



```

00247
00248 The following keys are supported in the `options` table:
00249
00250 | table key | value |
00251 | ----- | ----- |
00252 | `bootargs` | command line for guest kernel |
00253 | `cpus` | cpu mask |
00254 | `ext_args` | additional arguments to pass to UVMM |
00255 | `fdt` | file name of the device tree |
00256 | `id` | an integer identifying the VM |
00257 | `jdb` | jdb capability |
00258 | `kernel` | file name of the guest kernel binary |
00259 | `mem` | RAM size in MiB \e or dataspace cap for guest memory. |
00260 | `mem_align` | alignment for the guest memory in bits. Ignored if mem is a cap. |
00261 | `mon` | monitor application file name |
00262 | `net` | a virtio cap, e.g. for network |
00263 | `prio` | thread priority |
00264 | `ram_base` | start of guest memory |
00265 | `rd` | file name of the ramdisk |
00266 | `scheduler` | a scheduler cap. If used, prio and cpus are ignored. |
00267 | `vbus` | the vBus to attach to the VM |
00268 ]]
00269 function start_vm(options)
00270     local nr = options.id;
00271     local size_mb = 0;
00272     local vbus = options.vbus;
00273     local vnet = options.net;
00274     local prio = options.prio;
00275     local cpus = options.cpus;
00276     local scheduler = options.scheduler;
00277     local nonidentmem = options.nonidentmem;
00278
00279     local align = 10;
00280     if L4.Info.arch() == "arm" then
00281         align = 28;
00282     elseif L4.Info.arch() == "arm64" then
00283         align = 21;
00284     end
00285     align = options.mem_align or align;
00286
00287     local cmdline = {};
00288     if options.fdt then
00289         if type(options.fdt) ~= "table" then
00290             options.fdt = { options.fdt }
00291         end
00292         for _,v in ipairs(options.fdt) do
00293             cmdline[#cmdline+1] = "-d" .. v;
00294         end
00295     end
00296
00297     if options.bootargs then
00298         cmdline[#cmdline+1] = "-c" .. options.bootargs;
00299     end
00300
00301     if options.rd then
00302         cmdline[#cmdline+1] = "-r" .. options.rd;
00303     end
00304
00305     if options.kernel then
00306         cmdline[#cmdline+1] = "-k" .. options.kernel;
00307     end
00308
00309     if options.ram_base then
00310         cmdline[#cmdline+1] = "-b" .. options.ram_base;
00311     end
00312
00313     if L4.Info.arch() == "arm" or L4.Info.arch() == "arm64" then
00314         if not options.nonidentmem then
00315             cmdline[#cmdline+1] = "-i";
00316         end
00317     end
00318
00319     local keyb_shortcut = nil;
00320     if nr ~= nil then
00321         keyb_shortcut = "key=" .. nr;
00322     end
00323
00324     local vm_ram;
00325     if type(options.mem) == "userdata" then
00326         -- User gave us a cap. Using this as dataspace for guest RAM.
00327         vm_ram = options.mem
00328     elseif type(options.mem) == "number" then
00329         -- User gave us a number. Using this as size for a new Dataspace.
00330         size_mb = options.mem
00331     elseif type(options.mem) == "string" then
00332         print("start_vm: mem parameter '" .. options.mem .. "' is of type string, "
00333             .. "please use integer.");
00334     end

```

```

00334     size_mb = tonumber(options.mem)
00335 else
00336     -- User did not give us any valid value.
00337     size_mb = 16
00338 end
00339
00340 if size_mb > 0 then
00341     local mem_flags = L4.Mem_alloc_flags.Continuous
00342                     | L4.Mem_alloc_flags.Pinned
00343                     | L4.Mem_alloc_flags.Super_pages;
00344
00345     vm_ram = L4.Env.user_factory:create(L4.Proto.Dataspace,
00346                                       size_mb * 1024 * 1024,
00347                                       mem_flags, align):m("rw");
00348 end
00349
00350 local caps = {
00351     net = vnet;
00352     vbus = vbus;
00353     ram = vm_ram;
00354 };
00355
00356 if options.jdb then
00357     caps["jdb"] = L4.Env.jdb
00358 end
00359
00360 if options.ext_args then
00361     for _,v in ipairs(options.ext_args) do
00362         cmdline[#cmdline+1] = v
00363     end
00364 end
00365
00366 local opts = {
00367     log = options.log or l.log_fab:create(L4.Proto.Log, "vm" .. nr, "w",
00368                                         keyb_shortcut);
00369     caps = table_override(caps, options.ext_caps or {});
00370 };
00371
00372 if scheduler then
00373     opts["scheduler"] = scheduler;
00374 else
00375     set_sched(opts, prio, cpus);
00376 end
00377
00378 if type(options.mon) == 'string' then
00379     -- assume 'mon' is the name of a server binary which implements the uvmm
00380     -- CLI interface
00381     mon = l:new_channel()
00382
00383     l:start({
00384         scheduler = opts.scheduler;
00385         log = l.log_fab:create(L4.Proto.Log, "mon" .. nr),
00386         caps = { mon = mon:svr() }
00387     }, "rom/" .. options.mon)
00388
00389     opts.caps["mon"] = mon
00390 elseif options.mon ~= false then
00391     opts.caps["mon"] = l.log_fab:create(L4.Proto.Log, "mon" .. nr, "g");
00392 end
00393
00394 return l:startv(opts, "rom/uvmm", table.unpack(cmdline));
00395 end
00396
00397 return _ENV

```

## 16.43 debug.h

```

00001 /*
00002  * (c) 2013-2014 Alexander Warg <warg@os.inf.tu-dresden.de>
00003  *     economic rights: Technische Universität Dresden (Germany)
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007 #pragma once
00008
00009 #include <l4/re/util/debug>
00010
00011 struct Err : L4Re::Util::Err
00012 {
00013     Err(Level l = Fatal) : L4Re::Util::Err(l, "VSwitch") {}
00014 };
00015
00016 class Dbg : public L4Re::Util::Dbg

```

```

00017 {
00018     enum
00019     {
00020         Verbosity_shift = 4,
00021         Verbosity_mask = (1UL « Verbosity_shift) - 1
00022     };
00023
00024 public:
00025     enum Verbosity : unsigned long
00026     {
00027         Quiet = 0,
00028         Warn = 1,
00029         Info = 2,
00030         Debug = 4,
00031         Trace = 8,
00032         Max_verbosity = 8
00033     };
00034
00035     enum Component
00036     {
00037         Core = 0,
00038         Virtio,
00039         Port,
00040         Request,
00041         Queue,
00042         Packet,
00043         Max_component
00044     };
00045
00046 #ifndef NDEBUB
00047
00048     static_assert(Max_component * Verbosity_shift <= sizeof(level) * 8,
00049                   "Too many components for level mask");
00050     static_assert((Max_verbosity & Verbosity_mask) == Max_verbosity,
00051                   "Verbosity_shift to small for verbosity levels");
00052
00053     static void set_verbosity(unsigned mask)
00054     {
00055         for (unsigned i = 0; i < Max_component; ++i)
00056             set_verbosity(i, mask);
00057     }
00058
00059     static void set_verbosity(unsigned c, unsigned mask)
00060     {
00061         level &= ~(Verbosity_mask « (Verbosity_shift * c));
00062         level |= (mask & Verbosity_mask) « (Verbosity_shift * c);
00063     }
00064
00065     static bool is_active(unsigned c, unsigned mask)
00066     { return level & (mask & Verbosity_mask) « (Verbosity_shift * c); }
00067
00068     using L4Re::Util::Dbg::is_active;
00069
00070     Dbg(Component c = Core, Verbosity v = Warn, char const *subsys = nullptr)
00071     : L4Re::Util::Dbg(v « (Verbosity_shift * c), "SWI", subsys)
00072     {}
00073
00074 #else
00075
00076     static void set_verbosity(unsigned) {}
00077     static void set_verbosity(unsigned, unsigned) {}
00078
00079     static bool is_active(unsigned, unsigned) { return false; }
00080     using L4Re::Util::Dbg::is_active;
00081
00082     Dbg(Component c = Core, Verbosity v = Warn, char const *subsys = nullptr)
00083     : L4Re::Util::Dbg(v « (Verbosity_shift * c), "", subsys)
00084     {}
00085
00086 #endif
00087 };

```

## 16.44 l4/re/c/debug.h File Reference


Debug C interface.

```

#include <l4/sys/compiler.h>
#include <l4/sys/types.h>

```

Include dependency graph for debug.h:



## Functions

- [L4\\_BEGIN\\_DECLS](#) [l4\\_ret\\_t](#) [l4re\\_debug\\_obj\\_debug](#) ([l4\\_cap\\_idx\\_t](#) srv, unsigned long function) [L4\\_NOTHROW](#)  
Call debug function of [L4Re](#) service.

### 16.44.1 Detailed Description

Debug C interface.

Definition in file [debug.h](#).

## 16.45 debug.h

[Go to the documentation of this file.](#)

```

00001
00005 /*
00006  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>
00007  *     economic rights: Technische Universität Dresden (Germany)
00008  *
00009  * License: see LICENSE.spdx (in this directory or the directories above)
00010  */
00011 #pragma once
00012
00017
00018 #include <l4/sys/compiler.h>
00019 #include <l4/sys/types.h>
00020
00021 L4_BEGIN_DECLS
00022
00030 L4_CV l4_ret_t
00031 l4re_debug_obj_debug(l4_cap_idx_t srv, unsigned long function) L4_NOTHROW;
00032
00033 L4_END_DECLS

```

## 16.46 filter.cc

```

00001 /*
00002  * Copyright (C) 2016-2017, 2024 Kernkonzept GmbH.
00003  * Author(s): Jean Wolter <jean.wolter@kernkonzept.com>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007 #include "filter.h"
00008
00009 /* This is an example filter and therefore rather verbose. A real
00010    filter would not produce any output */
00011
00012 bool
00013 filter(const uint8_t *buf, size_t size)
00014 {
00015     // Packet large enough to apply filter condition?
00016     if (size <= 13)
00017         return false;
00018
00019     uint16_t ether_type = (uint16_t)*(buf + 12) << 8
00020                          | (uint16_t)*(buf + 13);
00021     char const *protocol;
00022     switch (ether_type)
00023     {
00024         case 0x0800: protocol = "IPv4"; break;
00025         case 0x0806: protocol = "ARP"; break;
00026         case 0x8100: protocol = "Vlan"; break;
00027         case 0x86dd: protocol = "IPv6"; break;
00028         case 0x8863: protocol = "PPPoE Discovery"; break;
00029         case 0x8864: protocol = "PPPoE Session"; break;
00030         default: protocol = nullptr;
00031     }
00032     if (protocol)
00033         printf("%s\n", protocol);
00034     else
00035         printf("%04x\n", ether_type);
00036
00037     if (ether_type == 0x0806)
00038     {
00039         printf("Do not filter arp\n");
00040         return false;
00041     }
00042
00043     return true;
00044 }

```

## 16.47 filter.h

```

00001 /*
00002  * Copyright (C) 2016-2017, 2023-2025 Kernkonzept GmbH.
00003  * Author(s): Jean Wolter <jean.wolter@kernkonzept.com>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007 #pragma once
00008
00009 #include "request.h"
00010 #include <l4/bid_config.h>
00011
00012 #ifndef CONFIG_VNS_PORT_FILTER
00013 bool filter(const uint8_t *buf, size_t size);
00014 #else
00015 inline bool filter(const uint8_t *, size_t)
00016 {
00017     // default implementation filtering out no packets, see filter.cc for
00018     // other examples
00019     return false;
00020 }
00021 #endif
00022
00023 inline bool filter_request(Net_request const &req)
00024 {
00025     size_t size;
00026     const uint8_t *buf = req.buffer(&size);
00027     return filter(buf, size);
00028 }

```

## 16.48 mac\_addr.h

```

00001 /*
00002  * Copyright (C) 2016-2017, 2020, 2022-2025 Kernkonzept GmbH.
00003  * Author(s): Jean Wolter <jean.wolter@kernkonzept.com>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007 #pragma once
00008
00009 #include <cstring>
00010 #include <inttypes.h>
00011
00012 class Mac_addr
00013 {
00014 public:
00015     enum
00016     {
00017         Addr_length = 6,
00018         Addr_unknown = 0ULL
00019     };
00020
00021     explicit Mac_addr(char const *_src)
00022     {
00023         /* A mac address is 6 bytes long, it is transmitted in big endian
00024            order over the network. For our internal representation we
00025            focus on easy testability of broadcast/multicast and reorder
00026            the bytes that the most significant byte becomes the least
00027            significant one. */
00028         unsigned char const *_src = reinterpret_cast<unsigned char const *>(_src);
00029         _mac = ((uint64_t)src[0]) | ((uint64_t)src[1]) << 8)
00030               | ((uint64_t)src[2]) << 16) | ((uint64_t)src[3]) << 24)
00031               | ((uint64_t)src[4]) << 32) | ((uint64_t)src[5]) << 40);
00032     }
00033
00034     static Mac_addr from_uncached(char volatile const *_src)
00035     { return Mac_addr(_src); }
00036
00037     explicit Mac_addr(uint64_t mac) : _mac{mac} {}
00038
00039     Mac_addr(Mac_addr const &other) : _mac{other._mac} {}
00040
00041     bool is_broadcast() const
00042     {
00043         /* There are broadcast and multicast addresses, both are supposed
00044            to be delivered to all station and the local network (layer 2).
00045
00046            Broadcast address is FF:FF:FF:FF:FF:FF, multicast addresses have
00047            the LSB of the first octet set. Since this holds for both
00048            broadcast and multicast we test for the multicast bit here.
00049
00050            In our internal representation we store the bytes in reverse
00051            order, so we test the least significant bit of the least
00052            significant byte.
00053         */
00054         return _mac & 1;
00055     }
00056
00057     bool is_unknown() const
00058     { return _mac == Addr_unknown; }
00059
00060     bool operator == (Mac_addr const &other) const
00061     { return _mac == other._mac; }
00062
00063     bool operator != (Mac_addr const &other) const
00064     { return _mac != other._mac; }
00065
00066     bool operator < (Mac_addr const &other) const
00067     { return _mac < other._mac; }
00068
00069     Mac_addr& operator = (Mac_addr const &other)
00070     { _mac = other._mac; return *this; }
00071
00072     Mac_addr& operator = (uint64_t mac)
00073     { _mac = mac; return *this; }
00074
00075     template<typename T>
00076     void print(T &stream) const
00077     {
00078         stream.printf("%02x:%02x:%02x:%02x:%02x:%02x",
00079                      (int)(_mac & 0xff), (int)((_mac >> 8) & 0xff),
00080                      (int)((_mac >> 16) & 0xff), (int)((_mac >> 24) & 0xff),
00081                      (int)((_mac >> 32) & 0xff), (int)((_mac >> 40) & 0xff));
00082     }
00083
00084     void to_array(unsigned char mac[6]) const

```

```

00094 {
00095     mac[0] = _mac & 0xffU;
00096     mac[1] = (_mac >> 8) & 0xffU;
00097     mac[2] = (_mac >> 16) & 0xffU;
00098     mac[3] = (_mac >> 24) & 0xffU;
00099     mac[4] = (_mac >> 32) & 0xffU;
00100     mac[5] = (_mac >> 40) & 0xffU;
00101 }
00102
00103 private:
00104     explicit Mac_addr(char volatile const *_src)
00105     {
00106         /* A mac address is 6 bytes long, it is transmitted in big endian
00107            order over the network. For our internal representation we
00108            focus on easy testability of broadcast/multicast and reorder
00109            the bytes that the most significant byte becomes the least
00110            significant one. */
00111         volatile unsigned char const *src = reinterpret_cast<volatile unsigned char const *>(_src);
00112         _mac = ((uint64_t)src[0]) | (((uint64_t)src[1]) << 8)
00113               | (((uint64_t)src[2]) << 16) | (((uint64_t)src[3]) << 24)
00114               | (((uint64_t)src[4]) << 32) | (((uint64_t)src[5]) << 40);
00115     }
00116     uint64_t _mac;
00117 };

```

## 16.49 mac\_table.h

```

00001 /*
00002  * Copyright (C) 2016-2017, 2020, 2022-2025 Kernkonzept GmbH.
00003  * Author(s): Jean Wolter <jean.wolter@kernkonzept.com>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007 #pragma once
00008
00009 #include "mac_addr.h"
00010 #include "port.h"
00011
00012 #include <array>
00013 #include <map>
00014 #include <tuple>
00015 #include <algorithm>
00020
00039 template<std::size_t Size = 1024U>
00040 class Mac_table
00041 {
00042 public:
00043     Mac_table()
00044     : _mac_table(),
00045       _entries(),
00046       _rr_index(0U)
00047     {}
00048
00058 Port_iface *lookup(Mac_addr dst, l4_uint16_t vlan_id) const
00059 {
00060     auto entry = _mac_table.find(std::tuple(dst, vlan_id));
00061     return (entry != _mac_table.end()) ? entry->second->port : nullptr;
00062 }
00063
00078 void learn(Mac_addr src, Port_iface *port, l4_uint16_t vlan_id)
00079 {
00080     Dbg info(Dbg::Port, Dbg::Info);
00081
00082     if (L4_UNLIKELY(info.is_active()))
00083     {
00084         // check whether we already know about src mac and vlan_id
00085         auto *p = lookup(src, vlan_id);
00086         if (!p || p != port)
00087         {
00088             info.printf("%s %-20s -> ", !p ? "learned " : "replaced",
00089                        port->get_name());
00090             src.print(info);
00091             info.cprintf("\n");
00092         }
00093     }
00094
00095     auto status = _mac_table.emplace(std::tuple(src, vlan_id),
00096                                     &_entries[_rr_index]);
00097     if (L4_UNLIKELY(status.second))
00098     {
00099         if (_entries[_rr_index].port)
00100         {

```

```

00101         // remove old entry
00102         _mac_table.erase(std::tuple(_entries[_rr_index].addr,
00103                                     _entries[_rr_index].vlan_id));
00104     }
00105     // Set/Replace port and mac address
00106     _entries[_rr_index].port = port;
00107     _entries[_rr_index].addr = src;
00108     _entries[_rr_index].vlan_id = vlan_id;
00109     _rr_index = (_rr_index + 1U) % Size;
00110 }
00111 else
00112 {
00113     // Update port to allow for movement of client between ports
00114     status.first->second->port = port;
00115 }
00116 }
00117
00129 void flush(Port_iface *port)
00130 {
00131     typedef std::pair<std::tuple<const Mac_addr, l4_uint16_t>, Entry*> TableEntry;
00132
00133     auto iter = _mac_table.begin();
00134     while ((iter = std::find_if(iter, _mac_table.end(),
00135                                [port](TableEntry const &p)
00136                                    { return p.second->port == port; })))
00137     {
00138         != _mac_table.end())
00139     {
00140         iter->second->port = nullptr;
00141         iter->second->addr = Mac_addr::Addr_unknown;
00142         iter->second->vlan_id = 0;
00143         iter = _mac_table.erase(iter);
00144     }
00145     assert(std::find_if(_mac_table.begin(), _mac_table.end(),
00146                        [port](TableEntry const &p)
00147                            { return p.second->port == port; }) == _mac_table.end());
00148 }
00149
00150 private:
00151 struct Entry {
00152     Port_iface *port;
00153     Mac_addr addr;
00154     l4_uint16_t vlan_id;
00155
00156     Entry()
00157     : port(nullptr),
00158       addr(Mac_addr::Addr_unknown),
00159       vlan_id(0)
00160     {}
00161 };
00162
00163 std::map<std::tuple<Mac_addr, l4_uint16_t>, Entry*> _mac_table;
00164 std::array<Entry, Size> _entries;
00165 size_t _rr_index;
00166 };

```

## 16.50 main.cc

```

00001 /*
00002  * Copyright (C) 2016-2020, 2022-2025 Kernkonzept GmbH.
00003  * Author(s): Jean Wolter <jean.wolter@kernkonzept.com>
00004  *            Manuel von Oltersdorff-Kalettka <manuel.kalettka@kernkonzept.com>
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00008 #include <l4/re/util/meta>
00009 #include <l4/re/util/object_registry>
00010 #include <l4/re/util/br_manager>
00011
00012 #include <l4/sys/factory>
00013 #include <l4/sys/task>
00014
00015 #include <l4/sys/cxx/ipc_epiface>
00016 #include <l4/sys/cxx/ipc_varg>
00017 #include <l4/cxx/dlist>
00018 #include <l4/cxx/string>
00019
00020 #include <stdlib.h>
00021 #include <string>
00022 #include <terminate_handler-l4>
00023 #include <vector>
00024
00025 #include "debug.h"

```



```

00026 #include "options.h"
00027 #include "switch.h"
00028 #include "vlan.h"
00029 #include <l4/virtio-net-switch/stats.h>
00030
00047
00048
00049 /*
00050  * Registry for our server, used to register
00051  * - factory capability
00052  * - irq object for capability deletion irqs
00053  * - virtio host kick irqs
00054  */
00055 static L4Re::Util::Registry_server<L4Re::Util::Br_manager_hooks> server;
00056
00057 using Ds_vector = std::vector<L4::Cap<L4Re::Dataspace>>;
00058 static std::shared_ptr<Ds_vector> trusted_dataspaces;
00059
00060 static bool
00061 parse_int_param(L4::Ipc::Varg const &param, char const *prefix, int *out)
00062 {
00063     l4_size_t headlen = strlen(prefix);
00064
00065     if (param.length() < headlen)
00066         return false;
00067
00068     char const *pstr = param.value<char const *>();
00069
00070     if (strncmp(pstr, prefix, headlen) != 0)
00071         return false;
00072
00073     std::string tail(pstr + headlen, param.length() - headlen);
00074
00075     if (!parse_int_optstring(tail.c_str(), out))
00076     {
00077         Err(Err::Normal).printf("Bad parameter '%s'. Invalid number specified.\n",
00078                                 prefix);
00079         throw L4::Runtime_error(-L4_EINVAL);
00080     }
00081
00082     return true;
00083 }
00084
00085 static void
00086 assign_random_mac(l4_uint8_t mac[6])
00087 {
00088     static bool initialized = false;
00089
00090     if (!initialized)
00091     {
00092         srand(l4_kip_clock(l4re_kip()));
00093         initialized = true;
00094     }
00095
00096     for (int i = 0; i < 6; i++)
00097         mac[i] = static_cast<l4_uint8_t>(random());
00098
00099     mac[0] &= ~(1U << 0); // clear multicast bit
00100     mac[0] |= 1U << 1;    // set "locally administered" bit
00101 }
00102
00114 class Switch_factory : public L4::Epiface_t<Switch_factory, L4::Factory>
00115 {
00119     class Port : public L4virtio_port
00120     {
00121     public:
00122         // Irq used to notify the guest
00123         L4::Cap<L4::Irq> _device_notify_irq;
00124
00125         L4::Cap<L4::Irq> device_notify_irq() const override
00126         { return _device_notify_irq; }
00127
00128         Port(unsigned vq_max, unsigned num_ds, char const *name,
00129              l4_uint8_t const *mac)
00130             : L4virtio_port(vq_max, num_ds, name, mac) {}
00131
00132         void register_end_points(L4Re::Util::Object_registry* registry,
00133                                 L4::Epiface *kick_irq)
00134         {
00135             // register virtio host kick irq
00136             _device_notify_irq = L4Re::chkcapi(registry->register_irq_obj(kick_irq));
00137
00138             // register virtio endpoint
00139             L4Re::chkcapi(registry->register_obj(this));
00140
00141             // decrement ref counter to get a notification when the last
00142             // external reference vanishes
00143         }
00144     };

```

```

00144     obj_cap()->dec_refcnt(1);
00145 }
00146
00147 virtual ~Port()
00148 { server.registry()->unregister_obj(this); }
00149 };
00150
00151 class Switch_port : public Port
00152 {
00153     class Kick_irq : public L4::Irqep_t<Kick_irq>
00154     {
00155     public:
00156         Virtio_switch *_switch;
00157         L4virtio_port *_port;
00158
00159         void handle_irq()
00160         { _switch->handle_l4virtio_port_tx(_port); }
00161
00162         Kick_irq(Virtio_switch *virtio_switch, L4virtio_port *port)
00163             : _switch(virtio_switch), _port{port} {}
00164     };
00165
00166     Kick_irq _kick_irq;
00167     Kick_irq _reschedule_tx_irq;
00168
00169 public:
00170     Switch_port(L4Re::Util::Object_registry *registry,
00171                 Virtio_switch *virtio_switch, unsigned vq_max, unsigned num_ds,
00172                 char const *name, l4_uint8_t const *mac)
00173         : Port(vq_max, num_ds, name, mac),
00174           _kick_irq(virtio_switch, this),
00175           _reschedule_tx_irq(virtio_switch, this)
00176     {
00177         register_end_points(registry, &_amp_kick_irq);
00178
00179         _pending_tx_reschedule =
00180             L4Re::chkcap(registry->register_irq_obj(&_reschedule_tx_irq),
00181                          "Register TX reschedule IRQ.");
00182         _pending_tx_reschedule->unmask();
00183     }
00184
00185     virtual ~Switch_port()
00186     {
00187         // We need to delete the IRQ object created in register_irq_obj() ourselves
00188         L4::Cap<L4::Task> (L4Re::This_task)
00189             ->unmap(_kick_irq.obj_cap().fpage(),
00190                    L4_FP_ALL_SPACES | L4_FP_DELETE_OBJ);
00191         server.registry()->unregister_obj(&_kick_irq);
00192
00193         L4::Cap<L4::Task> (L4Re::This_task)
00194             ->unmap(_pending_tx_reschedule.fpage(),
00195                    L4_FP_ALL_SPACES | L4_FP_DELETE_OBJ);
00196         server.registry()->unregister_obj(&_reschedule_tx_irq);
00197     }
00198 };
00199
00200 class Monitor_port : public Port
00201 {
00202     class Kick_irq : public L4::Irqep_t<Kick_irq>
00203     {
00204     public:
00205         void handle_irq()
00206         {
00207             do
00208             {
00209                 _port->tx_q()->disable_notify();
00210                 _port->rx_q()->disable_notify();
00211
00212                 _port->drop_requests();
00213
00214                 _port->tx_q()->enable_notify();
00215                 _port->rx_q()->enable_notify();
00216
00217                 L4virtio::wmb();
00218                 L4virtio::rmb();
00219             }
00220             while (_port->tx_work_pending());
00221         }
00222
00223         Kick_irq(L4virtio_port *port) : _port{port} {}
00224     };
00225
00226     Kick_irq _kick_irq;
00227
00228 public:

```

```

00265     Monitor_port(L4Re::Util::Object_registry* registry,
00266                 unsigned vq_max, unsigned num_ds, char const *name,
00267                 l4_uint8_t const *mac)
00268     : Port(vq_max, num_ds, name, mac), _kick_irq(this)
00269     { register_end_points(registry, &_kick_irq); }
00270
00271     virtual ~Monitor_port()
00272     {
00273         // We need to delete the IRQ object created in register_irq_obj() ourselves
00274         L4::Cap<L4::Task> (L4Re::This_task)
00275             ->unmap(_kick_irq.obj_cap().fpage(),
00276                   L4_FP_ALL_SPACES | L4_FP_DELETE_OBJ);
00277         server.registry()->unregister_obj(&_kick_irq);
00278     }
00279 };
00280
00281 class Stats_reader
00282 : public cxx::D_list_item,
00283   public L4::Epiface_t<Stats_reader, Virtio_net_switch::Statistics_if>
00284 {
00285     L4Re::Util::Unique_cap<L4Re::Dataspace> _ds;
00286     l4_addr_t _addr;
00287
00288 public:
00289     Stats_reader()
00290     {
00291         l4_size_t size = Switch_statistics::get_instance().size();
00292         _ds = L4Re::Util::make_unique_cap<L4Re::Dataspace>();
00293         L4Re::chksys(L4Re::Env::env()->mem_alloc()->alloc(size, _ds.get()),
00294                     "Could not allocate shared mem ds.");
00295         L4Re::chksys(L4Re::Env::env()->rm()->attach(&_addr, _ds->size(),
00296                                                     L4Re::Rm::F::Search_addr
00297                                                     | L4Re::Rm::F::RW,
00298                                                     L4::Ipc::make_cap_rw(_ds.get())));
00299         memset(reinterpret_cast<void*>(_addr), 0, _ds->size());
00300     }
00301
00302     ~Stats_reader()
00303     {
00304         L4Re::Env::env()->rm()->detach(reinterpret_cast<l4_addr_t>(_addr), 0);
00305         server.registry()->unregister_obj(this);
00306     }
00307
00308     long op_get_buffer(Virtio_net_switch::Statistics_if::Rights,
00309                      L4::Ipc::Cap<L4Re::Dataspace> &ds)
00310     {
00311         // We hand out the dataspace in a read only manner. Clients must not be
00312         // able to modify information as that would create an unwanted data
00313         // channel.
00314         ds = L4::Ipc::Cap<L4Re::Dataspace>(_ds.get(), L4_CAP_FPAGE_RO);
00315         return L4_EOK;
00316     }
00317
00318     long op_sync(Virtio_net_switch::Statistics_if::Rights)
00319     {
00320         memcpy(reinterpret_cast<void *>(_addr),
00321               reinterpret_cast<void *>(Switch_statistics::get_instance().stats()),
00322               Switch_statistics::get_instance().size());
00323         return L4_EOK;
00324     }
00325
00326     bool is_valid()
00327     { return obj_cap() && obj_cap().validate().label(); }
00328 };
00329
00330 class Stats_reader_list
00331 {
00332     cxx::D_list<Stats_reader> _readers;
00333
00334 public:
00335     void check_readers()
00336     {
00337         auto it = _readers.begin();
00338         while (it != _readers.end())
00339         {
00340             auto *reader = *it;
00341             if (!reader->is_valid())
00342             {
00343                 it = _readers.erase(it);
00344                 delete reader;
00345             }
00346             else
00347                 ++it;
00348         }
00349     }
00350 };

```

```

00355     void push_back(cxx::unique_ptr<Stats_reader> reader)
00356     {
00357         _readers.push_back(reader.release());
00358     }
00359 };
00360
00361 /*
00362  * Handle vanishing caps by telling the switch that a port might have gone
00363  */
00364 struct Del_cap_irq : public L4::Irqep_t<Del_cap_irq>
00365 {
00366 public:
00367     void handle_irq()
00368     {
00369         _switch->check_ports();
00370         _stats_readers->check_readers();
00371     }
00372
00373     Del_cap_irq(Virtio_switch *virtio_switch, Stats_reader_list *stats_readers)
00374     : _switch{virtio_switch},
00375       _stats_readers{stats_readers}
00376     {}
00377
00378 private:
00379     Virtio_switch *_switch;
00380     Stats_reader_list *_stats_readers;
00381 };
00382
00383 Virtio_switch *_virtio_switch;
00384
00386 unsigned _vq_max_num;
00387 Stats_reader_list _stats_readers;
00388 Del_cap_irq _del_cap_irq;
00393 unsigned _dbg_port_num = 0;
00394
00410 bool handle_opt_arg(L4::Ipc::Varg const &opt, bool &monitor,
00411                   char *name, size_t size,
00412                   l4_uint16_t &vlan_access,
00413                   std::vector<l4_uint16_t> &vlan_trunk,
00414                   bool *vlan_trunk_all,
00415                   l4_uint8_t mac[6], bool &mac_set)
00416 {
00417     assert(opt.is_of<char const *>());
00418     unsigned len = opt.length();
00419     const char *opt_str = opt.data();
00420     Err err(Err::Normal);
00421
00422
00423     if (len > 5)
00424     {
00425         if (!strcmp("type=", opt_str, 5))
00426         {
00427             if (!strcmp("type=monitor", opt_str, len))
00428             {
00429                 monitor = true;
00430                 return true;
00431             }
00432             else if (!strcmp("type=none", opt_str, len))
00433                 return true;
00434
00435             err.printf("Unknown type '%.*s'\n", opt.length() - 5, opt.data() + 5);
00436             return false;
00437         }
00438         else if (!strcmp("name=", opt_str, 5))
00439         {
00440             snprintf(name, size, "%.*s", opt.length() - 5, opt.data() + 5);
00441             return true;
00442         }
00443         else if (!strcmp("vlan=", opt_str, 5))
00444         {
00445             cxx::String str(opt_str + 5, strlen(opt_str + 5, len - 5));
00446             cxx::String::Index idx;
00447
00448             if ((idx = str.starts_with("access=")))
00449             {
00450                 str = str.substr(idx);
00451                 l4_uint16_t vid;
00452                 int next = str.from_dec(&vid);
00453                 if (next && next == str.len() && vlan_valid_id(vid))
00454                     vlan_access = vid;
00455                 else
00456                 {
00457                     err.printf("Invalid VLAN access port id '%.*s'\n",
00458                               opt.length(), opt.data());
00459                     return false;
00460                 }
00461             }

```

```

00462         else if ((idx = str.starts_with("trunk=")))
00463         {
00464             int next;
00465             l4_uint16_t vid;
00466             str = str.substr(idx);
00467             if (str == cxx::String("all"))
00468             {
00469                 *vlan_trunk_all = true;
00470                 return true;
00471             }
00472             while ((next = str.from_dec(&vid)))
00473             {
00474                 if (!vlan_valid_id(vid))
00475                     break;
00476                 vlan_trunk.push_back(vid);
00477                 if (next < str.len() && str[next] != ',')
00478                     break;
00479                 str = str.substr(next+1);
00480             }
00481
00482             if (vlan_trunk.empty() || !str.empty())
00483             {
00484                 err.printf("Invalid VLAN trunk port spec '%.s'\n",
00485                     opt.length(), opt.data());
00486                 return false;
00487             }
00488         }
00489         else
00490         {
00491             err.printf("Invalid VLAN specification..\n");
00492             return false;
00493         }
00494     }
00495     return true;
00496 }
00497 else if (!strncmp("mac=", opt_str, 4))
00498 {
00499     size_t const OPT_LEN = 4 /* mac= */ + 6*2 /* digits */ + 5 /* : */;
00500     // expect NUL terminated string for simplicity
00501     if (len > OPT_LEN && opt_str[OPT_LEN] == '\0' &&
00502         sscanf(opt_str+4, "%hhx:%hhx:%hhx:%hhx:%hhx:%hhx", &mac[0],
00503             &mac[1], &mac[2], &mac[3], &mac[4], &mac[5]) == 6)
00504     {
00505         mac_set = true;
00506         return true;
00507     }
00508
00509     err.printf("Invalid mac address '%.s'\n", len - 4, opt_str + 4);
00510     return false;
00511 }
00512 }
00513
00514 err.printf("Unknown option '%.s'\n", opt.length(), opt.data());
00515 return false;
00516 }
00517
00518 public:
00519 Switch_factory(Virtio_switch *virtio_switch, unsigned vq_max_num)
00520 : _virtio_switch(virtio_switch), _vq_max_num(vq_max_num),
00521   _del_cap_irq(virtio_switch, &stats_readers)
00522 {
00523     auto c = L4Re::chkcapi(server.registry()->register_irq_obj(&_del_cap_irq));
00524     L4Re::chksys(L4Re::Env::env()->main_thread()->register_del_irq(c));
00525 };
00526
00533 long op_create(L4::Factory::Rights, L4::Ipc::Cap<void> &res,
00534     l4_umword_t type, L4::Ipc::Varg_list_ref va)
00535 {
00536     switch (type)
00537     {
00538     case 0:
00539         return create_port(res, va);
00540     case 1:
00541         return create_stats(res);
00542     default:
00543         Dbg(Dbg::Core, Dbg::Warn).printf("op_create: Invalid object type\n");
00544         return -L4_EINVAL;
00545     }
00546 }
00547
00548 long create_port(L4::Ipc::Cap<void> &res, L4::Ipc::Varg_list_ref va)
00549 {
00550     Dbg warn(Dbg::Port, Dbg::Warn, "Port");
00551     Dbg info(Dbg::Port, Dbg::Info, "Port");
00552
00553     info.printf("Incoming port request\n");
00554

```

```

00555     bool monitor = false;
00556     char name[20] = "";
00557     unsigned arg_n = 2;
00558     l4_uint16_t vlan_access = 0;
00559     std::vector<l4_uint16_t> vlan_trunk;
00560     bool vlan_trunk_all = false;
00561
00562     l4_uint8_t mac[6];
00563     bool mac_set = false;
00564     int num_ds = 2;
00565
00566     for (L4::Ipc::Varg opt: va)
00567     {
00568         if (!opt.is_of<char const *>())
00569         {
00570             warn.printf("Unexpected type for argument %d\n", arg_n);
00571             return -L4_EINVAL;
00572         }
00573
00574         if (parse_int_param(opt, "ds-max=", &num_ds))
00575         {
00576             if (num_ds <= 0 || num_ds > 80)
00577             {
00578                 Err(Err::Normal).printf("warning: client requested invalid number"
00579                                         " of data spaces: 0 < %d <= 80\n", num_ds);
00580                 return -L4_EINVAL;
00581             }
00582         }
00583         else if (!handle_opt_arg(opt, monitor, name, sizeof(name), vlan_access,
00584                                 vlan_trunk, &vlan_trunk_all, mac, mac_set))
00585             return -L4_EINVAL;
00586
00587         ++arg_n;
00588     }
00589
00590     if (!_virtio_switch->port_available(monitor))
00591     {
00592         warn.printf("No port available\n");
00593         return -L4_ENOMEM;
00594     }
00595
00596     if (vlan_access && (!vlan_trunk.empty() || vlan_trunk_all))
00597     {
00598         warn.printf("VLAN port cannot be access and trunk simultaneously.\n");
00599         return -L4_EINVAL;
00600     }
00601
00602     if (!name[0])
00603         snprintf(name, sizeof(name), "%s[%u]", monitor ? "monitor": "",
00604                 _dbg_port_num++);
00605
00606     info.printf("    Creating port %s\n", name,
00607                monitor ? " as monitor port" : "");
00608
00609     // Assign a random MAC address if we assign one to our devices but the
00610     // user has not passed an explicit one for a port.
00611     if (!mac_set && Options::get_options()->assign_mac())
00612         assign_random_mac(mac);
00613
00614     l4_uint8_t *mac_ptr = (mac_set || Options::get_options()->assign_mac())
00615                          ? mac : nullptr;
00616
00617     // create port
00618     Port *port;
00619     if (monitor)
00620     {
00621         port = new Monitor_port(server.registry(), _vq_max_num, num_ds, name,
00622                                mac_ptr);
00623         port->set_monitor();
00624
00625         if (vlan_access)
00626             warn.printf("vlan=access=<id> ignored on monitor ports!\n");
00627         if (!vlan_trunk.empty())
00628             warn.printf("vlan=trunk=... ignored on monitor ports!\n");
00629     }
00630     else
00631     {
00632         port = new Switch_port(server.registry(), _virtio_switch, _vq_max_num,
00633                                num_ds, name, mac_ptr);
00634
00635         if (vlan_access)
00636             port->set_vlan_access(vlan_access);
00637         else if (vlan_trunk_all)
00638             port->set_vlan_trunk_all();
00639         else if (!vlan_trunk.empty())
00640             port->set_vlan_trunk(vlan_trunk);
00641     }

```

```

00642
00643     port->add_trusted_dataspaces(trusted_dataspaces);
00644     if (!trusted_dataspaces->empty())
00645         port->enable_trusted_ds_validation();
00646
00647     // hand port over to the switch
00648     bool added = monitor ? _virtio_switch->add_monitor_port(port)
00649                         : _virtio_switch->add_port(port);
00650     if (!added)
00651     {
00652         delete port;
00653         return -L4_ENOMEM;
00654     }
00655     res = L4::Ipc::make_cap(port->obj_cap(), L4_CAP_FPAGE_RWS);
00656
00657     info.printf("    Created port %s\n", name);
00658     return L4_EOK;
00659 }
00660
00661 long create_stats(L4::Ipc::Cap<void> &res)
00662 {
00663     // Create a stats reader and throw away our reference to get a notification
00664     // when the external reference vanishes.
00665     auto reader = cxx::make_unique<Stats_reader>();
00666     L4Re::chkcapi(server.registry()->register_obj(reader.get()));
00667     reader->obj_cap()->dec_refcnt(1);
00668     res = L4::Ipc::make_cap(reader->obj_cap(),
00669                             L4_CAP_FPAGE_R | L4_CAP_FPAGE_D);
00670     _stats_readers.push_back(cxx::move(reader));
00671     return L4_EOK;
00672 }
00673 };
00674
00675 #if CONFIG_VNS_IXL
00676 class Ixl_hw_port : public Ixl_port
00677 {
00678     template<typename Derived>
00679     class Port_irq : public L4::Irqp_t<Derived>
00680     {
00681     public:
00682         Port_irq(Virtio_switch *virtio_switch, Ixl_port *port)
00683             : _switch{virtio_switch}, _port{port} {}
00684     protected:
00685         Virtio_switch *_switch;
00686         Ixl_port *_port;
00687     };
00688
00689     class Receive_irq : public Port_irq<Receive_irq>
00690     {
00691     public:
00692         using Port_irq::Port_irq;
00693
00694         void handle_irq()
00695         {
00696             if (!_port->dev()->check_rcv_irq(0))
00697                 return;
00698
00699             if (_switch->handle_ixl_port_tx(_port))
00700                 _port->dev()->ack_rcv_irq(0);
00701         }
00702     };
00703
00704     class Reschedule_tx_irq : public Port_irq<Reschedule_tx_irq>
00705     {
00706     public:
00707         using Port_irq::Port_irq;
00708
00709         void handle_irq()
00710         {
00711             if (_switch->handle_ixl_port_tx(_port))
00712                 // Entire TX queue handled, re-enable the rcv IRQ again.
00713                 _port->dev()->ack_rcv_irq(0);
00714         }
00715     };
00716
00717     Receive_irq _rcv_irq;
00718     Reschedule_tx_irq _reschedule_tx_irq;
00719
00720 public:
00721     Ixl_hw_port(L4Re::Util::Object_registry *registry,
00722                 Virtio_switch *virtio_switch, Ixl::Ixl_device *dev)
00723         : Ixl_port(dev),
00724         _rcv_irq(virtio_switch, this),
00725         _reschedule_tx_irq(virtio_switch, this)
00726     {
00727         L4::Cap<L4::Irqp> rcv_irq_cap = L4Re::chkcapi(dev->get_rcv_irq(0), "Get receive IRQ");

```

```

00738     L4Re::chkcap(registry->register_obj(&recv_irq, recv_irq_cap),
00739                 "Register receive IRQ.");
00740     recv_irq_cap->unmask();
00741
00742     _pending_tx_reschedule =
00743         L4Re::chkcap(registry->register_irq_obj(&reschedule_tx_irq),
00744                     "Register TX reschedule IRQ.");
00745     _pending_tx_reschedule->unmask();
00746 }
00747
00748 ~Ixl_hw_port() override
00749 {
00750     server.registry()->unregister_obj(&recv_irq);
00751 }
00752 };
00753
00754 static void
00755 discover_ixl_devices(L4::Cap<L4vbus::Vbus> vbus, Virtio_switch *virtio_switch)
00756 {
00757     struct Ixl::Dev_cfg cfg;
00758     // Configure the device in asynchronous notify mode.
00759     cfg.irq_timeout_ms = -1;
00760
00761     // TODO: Support detecting multiple devices on a Vbus.
00762     // Setup the driver (also resets and initializes the NIC).
00763     Ixl::Ixl_device *dev = Ixl::Ixl_device::ixl_init(vbus, 0, cfg);
00764     if (!dev)
00765         // No Ixl supported device found, Ixl already printed an error message.
00766         return;
00767
00768     Ixl_hw_port *hw_port = new Ixl_hw_port(server.registry(), virtio_switch, dev);
00769     if (!virtio_switch->add_port(hw_port))
00770     {
00771         Err().printf("error adding ixl port\n");
00772         delete hw_port;
00773     }
00774 }
00775 #endif
00776
00777 int main(int argc, char *argv[])
00778 {
00779     trusted_dataspaces = std::make_shared<Ds_vector>();
00780     auto *opts = Options::parse_options(argc, argv, trusted_dataspaces);
00781     if (!opts)
00782     {
00783         Err().printf("Error during command line parsing.\n");
00784         return 1;
00785     }
00786
00787     // Show welcome message if debug level is not set to quiet
00788     if (Dbg(Dbg::Core, Dbg::Warn).is_active())
00789         printf("Hello from l4virtio switch\n");
00790
00791     Virtio_switch *virtio_switch = new Virtio_switch(opts->get_max_ports());
00792
00793 #ifdef CONFIG_VNS_STATS
00794     Switch_statistics::get_instance().initialize(opts->get_max_ports());
00795 #endif
00796
00797 #if CONFIG_VNS_IXL
00798     auto vbus = L4Re::Env::env()->get_cap<L4vbus::Vbus>("vbus");
00799     if (vbus.is_valid())
00800         discover_ixl_devices(vbus, virtio_switch);
00801 #endif
00802
00803     Switch_factory *factory = new Switch_factory(virtio_switch,
00804                                                  opts->get_virtq_max_num());
00805
00806     L4::Cap<void> cap = server.registry()->register_obj(factory, "svr");
00807     if (!cap.is_valid())
00808     {
00809         Err().printf("error registering switch\n");
00810         return 2;
00811     }
00812
00813     /*
00814     * server loop will handle 4 types of events
00815     * - Switch_factory
00816     *   - factory protocol
00817     *   - capability deletion
00818     *   - delegated to Virtio_switch::check_ports()
00819     * - Switch_factory::Switch_port
00820     *   - irqs triggered by clients
00821     *   - delegated to Virtio_switch::handle_l4virtio_port_tx()
00822     * - Virtio_net_transfer
00823     *   - timeouts for pending transfer requests added by
00824     *     Port_iface::handle_request() via registered via

```



```

00825      *      L4::Epiface::server_iface()->add_timeout()
00826      */
00827      server.loop();
00828      return 0;
00829  }
00830

```

## 16.51 Makefile

```

00001 PKGDIR = ..
00002 L4DIR ?= $(PKGDIR)/../..
00003
00004 PKGNAME = drivers
00005 PC_FILENAME = drivers-first
00006 EXTRA_TARGET += hw_mmio_register_block hw_register_block
00007
00008 include $(L4DIR)/mk/include.mk

```

## 16.52 Makefile

```

00001 PKGDIR = ../..
00002 L4DIR ?= $(PKGDIR)/../..
00003
00004 PKGNAME = drivers
00005
00006 include $(L4DIR)/mk/include.mk

```

## 16.53 Makefile

```

00001 PKGDIR = ../..
00002 L4DIR ?= $(PKGDIR)/../..
00003
00004 EXTRA_TARGET += cmd_control
00005
00006 include $(L4DIR)/mk/include.mk

```

## 16.54 Makefile

```

00001 PKGDIR      ?= ../..
00002 L4DIR      ?= $(PKGDIR)/../..
00003
00004 TARGET      = l4vio_switch
00005
00006 REQUIRES_LIBS = libstdc++ l4virtio
00007 REQUIRES_LIBS-$(CONFIG_VNS_IXL) += ixl
00008
00009 SRC_CC-$(CONFIG_VNS_PORT_FILTER) += filter.cc
00010
00011 SRC_CC = main.cc switch.cc options.cc
00012
00013 include $(L4DIR)/mk/prog.mk

```

## 16.55 options.cc

```

00001 /*
00002  * Copyright (C) 2016-2017, 2019, 2022-2025 Kernkonzept GmbH.
00003  * Author(s): Jean Wolter <jean.wolter@kernkonzept.com>
00004  *           Manuel von Oltersdorff-Kalettko <manuel.kalettko@kernkonzept.de>
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00008
00009 #include <getopt.h>
00010 #include <stdlib.h>

```

```

00011 #include <cstring>
00012 #include <type_traits>
00013
00014 #include <l4/cxx/exceptions>
00015 #include <l4/re/error_helper>
00016 #include <l4/re/env>
00017
00018 #include "debug.h"
00019 #include "options.h"
00020
00021 bool
00022 parse_int_optstring(char const *optstring, int *out)
00023 {
00024     char *endp;
00025
00026     errno = 0;
00027     long num = strtol(optstring, &endp, 10);
00028
00029     // check that long can be converted to int
00030     if (errno || *endp != '\0' || num < INT_MIN || num > INT_MAX)
00031         return false;
00032
00033     *out = num;
00034
00035     return true;
00036 }
00037
00038 static int
00039 verbosity_mask_from_string(char const *str, unsigned *mask)
00040 {
00041     if (strcmp("quiet", str) == 0)
00042     {
00043         *mask = Dbg::Quiet;
00044         return 0;
00045     }
00046     if (strcmp("warn", str) == 0)
00047     {
00048         *mask = Dbg::Warn;
00049         return 0;
00050     }
00051     if (strcmp("info", str) == 0)
00052     {
00053         *mask = Dbg::Warn | Dbg::Info;
00054         return 0;
00055     }
00056     if (strcmp("debug", str) == 0)
00057     {
00058         *mask = Dbg::Warn | Dbg::Info | Dbg::Debug;
00059         return 0;
00060     }
00061     if (strcmp("trace", str) == 0)
00062     {
00063         *mask = Dbg::Warn | Dbg::Info | Dbg::Debug | Dbg::Trace;
00064         return 0;
00065     }
00066
00067     return -L4_ENOENT;
00068 }
00069
00099 static void
00100 set_verbosity(char const *str)
00101 {
00102     unsigned mask;
00103     if (verbosity_mask_from_string(str, &mask) == 0)
00104     {
00105         Dbg::set_verbosity(mask);
00106         return;
00107     }
00108
00109     static char const *const components[] =
00110     { "core", "virtio", "port", "request", "queue", "packet" };
00111
00112     static_assert(std::extent<decltype(components)>::value == Dbg::Max_component,
00113         "Component names must match 'enum Component'.");
00114
00115     for (unsigned i = 0; i < Dbg::Max_component; ++i)
00116     {
00117         auto len = strlen(components[i]);
00118         if (strncmp(components[i], str, len) == 0 && str[len] == '='
00119             && verbosity_mask_from_string(str + len + 1, &mask) == 0)
00120         {
00121             Dbg::set_verbosity(i, mask);
00122             return;
00123         }
00124     }
00125 }
00126

```

```

00127 int
00128 Options::parse_cmd_line(int argc, char **argv,
00129                          std::shared_ptr<Ds_vector> trusted_dataspaces)
00130 {
00131     int opt, index;
00132
00133     struct option options[] =
00134     {
00135         {"size",          1, 0, 's' }, // size of in/out queue == #buffers in queue
00136         {"ports",         1, 0, 'p' }, // number of ports
00137         {"mac",           0, 0, 'm' }, // switch sets MAC address for each client
00138         {"debug",         1, 0, 'D' }, // configure debug levels
00139         {"verbose",       0, 0, 'v' },
00140         {"quiet",         0, 0, 'q' },
00141         {"register-ds",   1, 0, 'd' }, // register a trusted dataspace
00142         {0, 0, 0, 0}
00143     };
00144
00145     unsigned long verbosity = Dbg::Warn;
00146
00147     Dbg info(Dbg::Core, Dbg::Info);
00148
00149     Dbg::set_verbosity(Dbg::Core, Dbg::Info);
00150     info.printf("Arguments:\n");
00151     for (int i = 0; i < argc; ++i)
00152         info.printf("\t%s\n", argv[i]);
00153
00154     Dbg::set_verbosity(verbosity);
00155     while ( (opt = getopt_long(argc, argv, "s:p:mMqvD:d:", options, &index)) != -1)
00156     {
00157         switch (opt)
00158         {
00159             case 's':
00160
00161                 // QueueNumMax must be power of 2 between 1 and 0x8000
00162                 if (!parse_int_optstring(optarg, &_virtq_max_num)
00163                     || _virtq_max_num < 1 || _virtq_max_num > 32768
00164                     || (_virtq_max_num & (_virtq_max_num - 1)))
00165                 {
00166                     Err().printf("Max number of virtqueue buffers must be power of 2"
00167                                 " between 1 and 32768. Invalid value %i or argument "
00168                                 "%s\n",
00169                                 _virtq_max_num, optarg);
00169                     return -1;
00170                 }
00171                 info.printf("Max number of buffers in virtqueue: %i\n",
00172                             _virtq_max_num);
00173                 break;
00174             case 'p':
00175                 if (parse_int_optstring(optarg, &_max_ports))
00176                     info.printf("Max number of ports: %u\n", _max_ports);
00177                 else
00178                 {
00179                     Err().printf("Invalid number of ports argument: %s\n", optarg);
00180                     return -1;
00181                 }
00182                 break;
00183             case 'q':
00184                 verbosity = Dbg::Quiet;
00185                 Dbg::set_verbosity(verbosity);
00186                 break;
00187             case 'v':
00188                 verbosity = (verbosity << 1) | 1;
00189                 Dbg::set_verbosity(verbosity);
00190                 break;
00191             case 'D':
00192                 set_verbosity(optarg);
00193                 break;
00194             case 'm':
00195                 info.printf("Option -m ignored to compatibility.\n");
00196                 break;
00197             case 'M':
00198                 _assign_mac = false;
00199                 break;
00200             case 'd':
00201                 {
00202                     L4::Cap<L4Re::Dataspace> ds =
00203                         L4Re::chkcapi(L4Re::Env::env()->get_cap<L4Re::Dataspace>(optarg),
00204                                         "Find a dataspace capability.\n");
00205                     trusted_dataspaces->push_back(ds);
00206                     break;
00207                 }
00208             default:
00209                 Err().printf("Unknown command line option '%c' (%d)\n", opt, opt);
00210                 return -1;
00211         }
00212     }
00213 }

```

```

00214     return 0;
00215 }
00216
00217 static Options options;
00218
00219 Options const *
00220 Options::get_options()
00221 { return &options; }
00222
00223 Options const *
00224 Options::parse_options(int argc, char **argv,
00225                        std::shared_ptr<Ds_vector> trusted_dataspaces)
00226 {
00227     if (options.parse_cmd_line(argc, argv, trusted_dataspaces) < 0)
00228         return nullptr;
00229
00230     return &options;
00231 }

```

## 16.56 options.h

```

00001 /*
00002  * Copyright (C) 2016-2017, 2022, 2024-2025 Kernkonzept GmbH.
00003  * Author(s): Jean Wolter <jean.wolter@kernkonzept.com>
00004  *           Manuel von Oltersdorff-Kalettkka <manuel.kalettkka@kernkonzept.com>
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00008 #pragma once
00009
00010 #include <memory>
00011 #include <vector>
00012 #include <cerrno>
00013 #include <climits>
00014
00015 #include <l4/re/dataspace>
00016
00017 bool
00018 parse_int_optstring(char const *optstring, int *out);
00019
00020 class Options
00021 {
00022     using Ds_vector = std::vector<L4::Cap<L4Re::Dataspace>;
00023 public:
00024     int get_max_ports() const
00025     { return _max_ports; }
00026
00027     int get_virtq_max_num() const
00028     { return _virtq_max_num; }
00029
00030     int get_portq_max_num() const
00031     { return _portq_max_num; }
00032
00033     int get_request_timeout() const
00034     { return _request_timeout; }
00035
00036     int assign_mac() const
00037     { return _assign_mac; }
00038
00039     static Options const *
00040     parse_options(int argc, char **argv,
00041                  std::shared_ptr<Ds_vector> trusted_dataspaces);
00042     static Options const *get_options();
00043
00044 private:
00045     int _max_ports = 256;
00046     int _virtq_max_num = 0x100; // default value for data queues
00047     int _portq_max_num = 50;    // default value for port queues
00048     int _request_timeout = 1 * 1000 * 1000; // default packet timeout 1 second
00049     bool _assign_mac = true;
00050
00051     int parse_cmd_line(int argc, char **argv,
00052                       std::shared_ptr<Ds_vector> trusted_dataspaces);
00053 };

```

## 16.57 port.h

```

00001 /*

```

```

00002  * Copyright (C) 2016-2018, 2020, 2022-2025 Kernkonzept GmbH.
00003  * Author(s): Jean Wolter <jean.wolter@kernkonzept.com>
00004  *           Alexander Warg <warg@os.inf.tu-dresden.de>
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00008 #pragma once
00009
00010 #include "request.h"
00011 #include "mac_addr.h"
00012 #include "vlan.h"
00013 #include "stats.h"
00014
00015 #include <cassert>
00016 #include <set>
00017 #include <vector>
00018
00023
00024 class Port_iface
00025 {
00026 protected:
00027     Virtio_net_switch::Port_statistics *_stats;
00028
00029 public:
00030     Port_iface(char const *name)
00031     {
00032         strncpy(_name, name, sizeof(_name));
00033         _name[sizeof(_name) - 1] = '\0';
00034 #ifdef CONFIG_VNS_STATS
00035         _stats = Switch_statistics::get_instance().allocate_port_statistics(name);
00036         if (!_stats)
00037             throw L4::Runtime_error(-L4_ENOMEM,
00038                                     "Could not allocate port statistics.\n");
00039 #endif
00040     }
00041
00042     virtual ~Port_iface()
00043     {
00044 #ifdef CONFIG_VNS_STATS
00045         _stats->in_use = false;
00046 #endif
00047     }
00048
00049     // delete copy and assignment
00050     Port_iface(Port_iface const &) = delete;
00051     Port_iface &operator = (Port_iface const &) = delete;
00052
00053     char const *get_name() const
00054     { return _name; }
00055
00056     l4_uint16_t get_vlan() const
00057     { return _vlan_id; }
00058
00059     inline bool is_trunk() const
00060     { return _vlan_id == VLAN_ID_TRUNK; }
00061
00062     inline bool is_native() const
00063     { return _vlan_id == VLAN_ID_NATIVE; }
00064
00065     inline bool is_access() const
00066     { return !is_trunk() && !is_native(); }
00067
00075     void set_vlan_access(l4_uint16_t id)
00076     {
00077         assert(vlan_valid_id(id));
00078         _vlan_id = id;
00079         _vlan_bloom_filter = 0;
00080         _vlan_ids.clear();
00081     }
00082
00092     void set_vlan_trunk(const std::vector<l4_uint16_t> &ids)
00093     {
00094         // bloom filter to quickly reject packets that do not belong to this port
00095         l4_uint32_t filter = 0;
00096
00097         _vlan_ids.clear();
00098         for (const auto id : ids)
00099         {
00100             assert(vlan_valid_id(id));
00101             filter |= vlan_bloom_hash(id);
00102             _vlan_ids.insert(id);
00103         }
00104
00105         _vlan_id = VLAN_ID_TRUNK;
00106         _vlan_bloom_filter = filter;
00107     }
00108

```

```

00112 void set_vlan_trunk_all()
00113 {
00114     _vlan_all = true;
00115     _vlan_id = VLAN_ID_TRUNK;
00116     _vlan_bloom_filter = -1;
00117 }
00118
00125 void set_monitor()
00126 {
00127     _vlan_id = VLAN_ID_TRUNK;
00128     _vlan_bloom_filter = 0;
00129 }
00130
00139 bool match_vlan(uint16_t id)
00140 {
00141     // Regular case native/access port
00142     if (id == _vlan_id)
00143         return true;
00144
00145     // This port participates in all VLANs
00146     if (_vlan_all)
00147         return true;
00148
00149     // Quick check: does port probably accept this VLAN?
00150     if ((_vlan_bloom_filter & vlan_bloom_hash(id)) == 0)
00151         return false;
00152
00153     return _vlan_ids.find(id) != _vlan_ids.end();
00154 }
00155
00162 inline Mac_addr mac() const
00163 { return _mac; }
00164
00165 Virtio_vlan_mangle create_vlan_mangle(Port_iface *src_port) const
00166 {
00167     Virtio_vlan_mangle mangle;
00168
00169     if (is_trunk())
00170     {
00171         /*
00172          * Add a VLAN tag only if the packet does not already have one (by
00173          * coming from another trunk port) or if the packet does not belong to
00174          * any VLAN (by coming from a native port). The latter case is only
00175          * relevant if this is a monitor port. Otherwise traffic from native
00176          * ports is never forwarded to trunk ports.
00177          */
00178         if (!src_port->is_trunk() && !src_port->is_native())
00179             mangle = Virtio_vlan_mangle::add(src_port->get_vlan());
00180     }
00181     else
00182     {
00183         /*
00184          * Remove VLAN tag only if the packet actually has one (by coming from a
00185          * trunk port).
00186          */
00187         if (src_port->is_trunk())
00188             mangle = Virtio_vlan_mangle::remove();
00189     }
00190     return mangle;
00191 }
00192
00192 virtual void rx_notify_disable_and_remember() = 0;
00193 virtual void rx_notify_emit_and_enable() = 0;
00194
00195 virtual bool is_gone() const = 0;
00196
00198 // std::optional<Net_request> get_tx_request() = 0;
00199
00200 enum class Result
00201 {
00202     Delivered, Exception, Dropped,
00203 };
00204
00220 virtual Result handle_request(Port_iface *src_port,
00221                               Net_transfer &src,
00222                               l4_uint64_t *bytes_transferred) = 0;
00223
00224 void reschedule_pending_tx()
00225 { _pending_tx_reschedule->trigger(); }
00226
00227 protected:
00228     /*
00229      * VLAN related management information.
00230      *
00231      * A port may either be
00232      * - a native port (_vlan_id == VLAN_ID_NATIVE), or
00233      * - an access port (_vlan_id set accordingly), or
00234      * - a trunk port (_vlan_id == VLAN_ID_TRUNK, _vlan_bloom_filter and

```

```

00235     *    _vlan_ids populated accordingly, or _vlan_all == true).
00236     */
00237     l4_uint16_t _vlan_id = VLAN_ID_NATIVE; // VID for native/access port
00238     l4_uint32_t _vlan_bloom_filter = 0; // Bloom filter for trunk ports
00239     std::set<l4_uint16_t> _vlan_ids; // Authoritative list of trunk VLANs
00240     bool _vlan_all; // This port participates in all VLANs (ignoring _vlan_ids)
00241
00242     inline l4_uint32_t vlan_bloom_hash(l4_uint16_t vid)
00243     { return 1UL < (vid & 31U); }
00244
00245     L4::Cap<L4::Irq> _pending_tx_reschedule;
00246
00247     Mac_addr _mac = Mac_addr(Mac_addr::Addr_unknown);
00248     char _name[20];
00249
00250 public:
00251 #ifndef CONFIG_VNS_STATS
00252     inline void stat_inc_tx_num()
00253     { _stats->tx_num++; }
00254     inline void stat_inc_tx_dropped()
00255     { _stats->tx_dropped++; }
00256     inline void stat_inc_tx_bytes(l4_uint64_t bytes)
00257     { _stats->tx_bytes += bytes; }
00258     inline void stat_inc_rx_num()
00259     { _stats->rx_num++; }
00260     inline void stat_inc_rx_dropped()
00261     { _stats->rx_dropped++; }
00262     inline void stat_inc_rx_bytes(l4_uint64_t bytes)
00263     { _stats->rx_bytes += bytes; }
00264 #else
00265     inline void stat_inc_tx_num()
00266     {}
00267     inline void stat_inc_tx_dropped()
00268     {}
00269     inline void stat_inc_tx_bytes(l4_uint64_t /*bytes*/)
00270     {}
00271     inline void stat_inc_rx_num()
00272     {}
00273     inline void stat_inc_rx_dropped()
00274     {}
00275     inline void stat_inc_rx_bytes(l4_uint64_t /*bytes*/)
00276     {}
00277 #endif
00278 };
00279
00280
00281

```

## 16.58 port\_ixl.h

```

00001 /*
00002  * Copyright (C) 2024-2025 Kernkonzept GmbH.
00003  * Author(s): Georg Kotheimer <georg.kotheimer@kernkonzept.com>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007 #pragma once
00008
00009 #include "port.h"
00010 #include "request_ixl.h"
00011
00012 #include <l4/ixl/device.h>
00013 #include <l4/ixl/memory.h>
00014
00015 #include <optional>
00016
00017
00018 class Ixl_port : public Port_iface
00019 {
00020 public:
00021     static constexpr unsigned Tx_batch_size = 32;
00022     static constexpr unsigned Num_bufs = 1024;
00023     static constexpr unsigned Buf_size = 2048;
00024     static constexpr l4_uint64_t Max_mem_size = 1ULL < 28;
00025
00026     Ixl_port(Ixl::Ixl_device *dev)
00027     : Port_iface(dev->get_driver_name().c_str()),
00028       _dev(dev),
00029       _mempool(*_dev, Num_bufs, Buf_size, Max_mem_size)
00030     {
00031         Ixl::mac_address mac_addr = _dev->get_mac_addr();
00032         _mac = Mac_addr(reinterpret_cast<char const *>(mac_addr.addr));
00033     }
00034     #if CONFIG_VNS_STATS
00035         _mac.to_array(_stats->mac);
00036     #endif
00037

```

```

00040     }
00041
00042     // OPTIMIZE: Could use this information for rx batching, i.e. collect while
00043     //             rx_notify is disabled, then flush the collected buffers when
00044     //             rx_notify is enabled again.
00045     void rx_notify_disable_and_remember() override {}
00046     void rx_notify_emit_and_enable() override {}
00047     bool is_gone() const override { return false; }
00048
00049     bool tx_work_pending()
00050     {
00051         fetch_tx_requests();
00052         return _tx_batch_idx < _tx_batch_len;
00053     }
00054
00055     std::optional<Ixl_net_request> get_tx_request()
00056     {
00057         fetch_tx_requests();
00058         if (_tx_batch_idx < _tx_batch_len)
00059             return std::make_optional<Ixl_net_request>(_tx_batch[_tx_batch_idx++]);
00060         else
00061             return std::nullopt;
00062     }
00063
00064     Result handle_request(Port_iface *src_port, Net_transfer &src,
00065                          l4_uint64_t *bytes_transferred) override
00066     {
00067         Virtio_vlan_mangle mangle = create_vlan_mangle(src_port);
00068
00069         Dbg trace(Dbg::Request, Dbg::Trace, "REQ-IXL");
00070         trace.printf("%s: Transfer request %p.\n", _name, src.req_id());
00071
00072         struct Ixl::pkt_buf *buf = _mempool.pkt_buf_alloc();
00073         if (!buf)
00074         {
00075             trace.printf("\tTransfer failed, out-of-memory, dropping.\n");
00076             return Result::Dropped;
00077         }
00078
00079         // NOTE: Currently, the switch does not offer checksum or segmentation
00080         //         offloading to its l4virtio clients, so it is fine to simply ignore
00081         //         the Virtio_net::Hdr of the request here.
00082
00083         // Copy the request to the pkt_buf.
00084         Buffer dst_buf(reinterpret_cast<char *>(buf->data),
00085                      Buf_size - offsetof(Ixl::pkt_buf, data));
00086         unsigned max_size = Buf_size - offsetof(Ixl::pkt_buf, data);
00087         for (;;)
00088         {
00089             try
00090             {
00091                 if (src.done())
00092                     // Request completely copied to destination.
00093                     break;
00094             }
00095             catch (L4virtio::Svr::Bad_descriptor &e)
00096             {
00097                 trace.printf("\tTransfer failed, bad descriptor exception, dropping.\n");
00098
00099                 // Handle partial transfers to destination port.
00100                 Ixl::pkt_buf_free(buf);
00101                 throw;
00102             }
00103
00104             if (dst_buf.done())
00105             {
00106                 trace.printf(
00107                     "\tTransfer failed, exceeds max packet-size, dropping.\n");
00108                 Ixl::pkt_buf_free(buf);
00109                 return Result::Dropped;
00110             }
00111
00112             auto &src_buf = src.cur_buf();
00113             trace.printf("\tCopying %p#%p:%u (%x) -> %p#%p:%u (%x)\n",
00114                          src_port, src_buf.pos, src_buf.left, src_buf.left,
00115                          static_cast<Port_iface *>(this),
00116                          dst_buf.pos, dst_buf.left, dst_buf.left);
00117
00118             mangle.copy_pkt(dst_buf, src_buf);
00119         }
00120         buf->size = max_size - dst_buf.left;
00121         *bytes_transferred = buf->size;
00122
00123         // Enqueue the pkt_buf at the device.
00124         if (_dev->tx_batch(0, &buf, 1) == 1)
00125         {
00126             trace.printf("\tTransfer queued at device.\n");
00127         }
00128     }

```



```

00129         return Result::Delivered;
00130     }
00131     else
00132     {
00133         trace.printf("\tTransfer failed, dropping.\n");
00134         Ix1::pkt_buf_free(buf);
00135         return Result::Dropped;
00136     }
00137 }
00138
00139 Ix1::Ix1_device *dev() { return _dev; }
00140
00141 private:
00142 void fetch_tx_requests()
00143 {
00144     if (_tx_batch_idx < _tx_batch_len)
00145         // Previous batch not yet fully processed.
00146         return;
00147
00148     // Batch receive, then cache in member array, to avoid frequent interactions
00149     // with the hardware.
00150     _tx_batch_len = _dev->rx_batch(0, _tx_batch, Tx_batch_size);
00151     _tx_batch_idx = 0;
00152 }
00153
00154 Ix1::Ix1_device *_dev;
00155 Ix1::Mempool _mempool;
00156 Ix1::pkt_buf *_tx_batch[Tx_batch_size];
00157 unsigned _tx_batch_idx = 0;
00158 unsigned _tx_batch_len = 0;
00159 };
00160

```

## 16.59 port\_l4virtio.h

```

00001 /*
00002  * Copyright (C) 2016-2017, 2020, 2022-2025 Kernkonzept GmbH.
00003  * Author(s): Jean Wolter <jean.wolter@kernkonzept.com>
00004  *            Alexander Warg <warg@os.inf.tu-dresden.de>
00005  *            Georg Kotheimer <georg.kotheimer@kernkonzept.com>
00006  *
00007  * License: see LICENSE.spdx (in this directory or the directories above)
00008  */
00009 #pragma once
00010
00011 #include "port.h"
00012 #include "request_l4virtio.h"
00013 #include "virtio_net.h"
00014
00015 #include <l4/cxx/pair>
00016
00017 #include <vector>
00018
00023
00036 class L4virtio_port : public Port_iface, public Virtio_net
00037 {
00038 public:
00042     explicit L4virtio_port(unsigned vq_max, unsigned num_ds, char const *name,
00043                           l4_uint8_t const *mac)
00044     : Port_iface(name), Virtio_net(vq_max)
00045     {
00046         init_mem_info(num_ds);
00047
00048         Features hf = _dev_config.host_features(0);
00049         if (mac)
00050         {
00051             _mac = Mac_addr((char const *)mac);
00052             memcpy((void *)_dev_config.priv_config()->mac, mac,
00053                   sizeof(_dev_config.priv_config()->mac));
00054
00055             hf.mac() = true;
00056             Dbg d(Dbg::Port, Dbg::Info);
00057             d.cprintf("%s: Adding Mac '", _name);
00058             _mac.print(d);
00059             d.cprintf("' to host features to %x\n", hf.raw);
00060         }
00061         _dev_config.host_features(0) = hf.raw;
00062         _dev_config.reset_hdr();
00063         Dbg(Dbg::Port, Dbg::Info)
00064             .printf("%s: Set host features to %x\n", _name,
00065                   _dev_config.host_features(0));
00066 #if CONFIG_VNS_STATS
00067         _mac.to_array(_stats->mac);

```

```

00068 #endif
00069 }
00070
00071 void rx_notify_disable_and_remember() override
00072 {
00073     kick_disable_and_remember();
00074 }
00075
00076 void rx_notify_emit_and_enable() override
00077 {
00078     kick_emit_and_enable();
00079 }
00080
00081 bool is_gone() const override
00082 {
00083     return obj_cap() && !obj_cap().validate().label();
00084 }
00085
00086 bool tx_work_pending() const
00087 {
00088     return L4_LIKELY(tx_q()->ready()) && tx_q()->desc_avail();
00089 }
00090
00091 std::optional<Virtio_net_request> get_tx_request()
00092 {
00093     return Virtio_net_request::get_request(this, tx_q());
00094 }
00095
00096 void drop_requests()
00097 {
00098     Virtio_net_request::drop_requests(this, tx_q());
00099 }
00100
00101 Result handle_request(Port_iface *src_port, Net_transfer &src,
00102                      l4_uint64_t *bytes_transferred) override
00103 {
00104     Virtio_vlan_mangle mangle = create_vlan_mangle(src_port);
00105
00106     Dbg trace(Dbg::Request, Dbg::Trace, "REQ-VIO");
00107     trace.printf("%s: Transfer request %p.\n", _name, src.req_id());
00108
00109     Buffer dst;
00110     int total = 0;
00111     l4_uint16_t num_merged = 0;
00112     l4_uint64_t total_merged = 0;
00113     typedef cxx::Pair<L4virtio::Svr::Virtqueue::Head_desc, l4_uint32_t> Consumed_entry;
00114     std::vector<Consumed_entry> consumed;
00115
00116     Virtio_net *dst_dev = this;
00117     Virtqueue *dst_queue = rx_q();
00118     L4virtio::Svr::Virtqueue::Head_desc dst_head;
00119     L4virtio::Svr::Request_processor dst_req_proc;
00120     Virtio_net::Hdr *dst_header = nullptr;
00121
00122     for (;;)
00123     {
00124         try
00125         {
00126             if (src.done())
00127                 // Request completely copied to destination.
00128                 break;
00129         }
00130         catch (L4virtio::Svr::Bad_descriptor &e)
00131         {
00132             trace.printf("\tTransfer failed, bad descriptor exception, dropping.\n");
00133
00134             // Handle partial transfers to destination port.
00135             if (!consumed.empty())
00136                 // Partial transfer, rewind to before first descriptor of transfer.
00137                 dst_queue->rewind_avail(consumed.at(0).first);
00138             else if (dst_head)
00139                 // Partial transfer, still at first _dst_head.
00140                 dst_queue->rewind_avail(dst_head);
00141             throw;
00142         }
00143     }
00144
00145     /* The source data structures are already initialized, the header
00146        is consumed and src stands at the very first real buffer.
00147        Initialize the target data structures if necessary and fill the
00148        header. */
00149     if (!dst_head)
00150     {
00151         if (!dst_queue->ready())
00152             return Result::Dropped;
00153
00154         auto r = dst_queue->next_avail();
00155
00156         if (L4_UNLIKELY(!r))
00157         {

```

```

00162         trace.printf("\tTransfer failed, destination queue depleted, dropping.\n");
00163         // Abort incomplete transfer.
00164         if (!consumed.empty())
00165             dst_queue->rewind_avail(consumed.front().first);
00166         return Result::Dropped;
00167     }
00168
00169     try
00170     {
00171         dst_head = dst_req_proc.start(dst_dev->mem_info(), r, &dst);
00172     }
00173     catch (L4virtio::Svr::Bad_descriptor &e)
00174     {
00175         Dbg(Dbg::Request, Dbg::Warn, "REQ")
00176             .printf("%s: bad descriptor exception: %s - %i"
00177                 " -- signal device error in destination device %p.\n",
00178                 __PRETTY_FUNCTION__, e.message(), e.error, dst_dev);
00179
00180         dst_dev->device_error();
00181         return Result::Exception; // Must not touch the dst queues anymore.
00182     }
00183
00184     if (!dst_header)
00185     {
00186         if (dst.left < sizeof(Virtio_net::Hdr))
00187             throw L4::Runtime_error(-L4_EINVAL,
00188                 "Target buffer too small for header");
00189         dst_header = reinterpret_cast<Virtio_net::Hdr *>(dst.pos);
00190         trace.printf("\tCopying header to %p (size: %u)\n",
00191             dst.pos, dst.left);
00192
00193         /*
00194          * Header and csum offloading/general segmentation offloading
00195          *
00196          * We just copy the original header from source to
00197          * destination and have to consider three different
00198          * cases:
00199          * - no flags are set
00200          *   - we got a packet that is completely checksummed
00201          *     and correctly fragmented, there is nothing to
00202          *     do other than copying.
00203          * - virtio_net_hdr_f_needs_csum set
00204          *   - the packet is partially checksummed; if we would
00205          *     send the packet out on the wire we would have
00206          *     to calculate checksums now. But here we rely on
00207          *     the ability of our guest to handle partially
00208          *     checksummed packets and simply delegate the
00209          *     checksum calculation to them.
00210          * - gso_type != gso_none
00211          *   - the packet needs to be segmented; if we would
00212          *     send it out on the wire we would have to
00213          *     segment it now. But again we rely on the
00214          *     ability of our guest to handle gso
00215          *
00216          * We currently assume that our guests negotiated
00217          * virtio_net_f_guest_*, this needs to be checked in
00218          * the future.
00219          *
00220          * We also discussed the usage of
00221          * virtio_net_hdr_f_data_valid to remove the need to
00222          * checksum packets at all. But since our clients send
00223          * partially checksummed packets anyway the only
00224          * interesting case would be a packet without
00225          * net_hdr_f_needs_checksum set. In that case we would
00226          * signal that we checked the checksum and the
00227          * checksum is actually correct. Since we do not know
00228          * the origin of the packet (it could have been send
00229          * by an external node and could have been routed to
00230          * u) we can not signal this without actually
00231          * verifying the checksum. Otherwise a packet with an
00232          * invalid checksum could be successfully delivered.
00233          */
00233         total = sizeof(Virtio_net::Hdr);
00234         src.copy_header(dst_header);
00235         mangle.rewrite_hdr(dst_header);
00236         dst.skip(total);
00237     }
00238     ++num_merged;
00239 }
00240
00241 bool has_dst_buffer = !dst.done();
00242 if (!has_dst_buffer)
00243     try
00244     {
00245         // The current dst buffer is full, try to get next chained buffer.
00246         has_dst_buffer = dst_req_proc.next(dst_dev->mem_info(), &dst);
00247     }
00248     catch (L4virtio::Svr::Bad_descriptor &e)

```

```

00249         {
00250             Dbg(Dbg::Request, Dbg::Warn, "REQ")
00251             .printf("%s: bad descriptor exception: %s - %i"
00252                 " -- signal device error in destination device %p.\n",
00253                 __PRETTY_FUNCTION__, e.message(), e.error, dst_dev);
00254             dst_dev->device_error();
00255             return Result::Exception; // Must not touch the dst queues anymore.
00256         }
00257
00258     if (has_dst_buffer)
00259     {
00260         auto &src_buf = src.cur_buf();
00261         trace.printf("\tCopying %p#%p:%u (%x) -> %p#%p:%u (%x)\n",
00262             src_port, src_buf.pos, src_buf.left, src_buf.left,
00263             static_cast<Port_iface *>(this),
00264             dst.pos, dst.left, dst.left);
00265
00266         total += mangle.copy_pkt(dst, src_buf);
00267     }
00268     else if (negotiated_features().mrg_rxbuf())
00269     {
00270         // save descriptor information for later
00271         trace.printf("\tSaving descriptor for later\n");
00272         consumed.push_back(Consumed_entry(dst_head, total));
00273         total_merged += total;
00274         total = 0;
00275         dst_head = L4virtio::Svr::Virtqueue::Head_desc();
00276     }
00277     else
00278     {
00279         trace.printf("\tTransfer failed, destination buffer too small, dropping.\n");
00280         // Abort incomplete transfer.
00281         dst_queue->rewind_avail(dst_head);
00282         return Result::Dropped;
00283     }
00284 }
00285
00286 /*
00287  * Finalize the Request delivery. Call `finish()` on the destination
00288  * port's receive queue, which will result in triggering the destination
00289  * client IRQ.
00290  */
00291
00292 if (!dst_header)
00293 {
00294     if (!total)
00295         trace.printf("\tTransfer - not started yet, dropping\n");
00296     return Result::Dropped;
00297 }
00298
00299 if (consumed.empty())
00300 {
00301     assert(dst_head);
00302     assert(num_merged == 1);
00303     trace.printf("\tTransfer - Invoke dst_queue->finish()\n");
00304     dst_header->num_buffers = 1;
00305     dst_queue->finish(dst_head, dst_dev, total);
00306     *bytes_transferred = total;
00307 }
00308 else
00309 {
00310     assert(dst_head);
00311     dst_header->num_buffers = num_merged;
00312     consumed.push_back(Consumed_entry(dst_head, total));
00313     trace.printf("\tTransfer - Invoke dst_queue->finish(iter)\n");
00314     *bytes_transferred = total + total_merged;
00315     dst_queue->finish(consumed.begin(), consumed.end(), dst_dev);
00316 }
00317 return Result::Delivered;
00318 }
00319 };
00320

```

## 16.60 request.h

```

00001 /*
00002  * Copyright (C) 2016-2017, 2020, 2022, 2024-2025 Kernkonzept GmbH.
00003  * Author(s): Jean Wolter <jean.wolter@kernkonzept.com>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007 #pragma once
00008

```

```

00009 #include "mac_addr.h"
00010 #include "virtio_net.h"
00011 #include "virtio_net_buffer.h"
00012 #include "vlan.h"
00013
00014 #include <l4/l4virtio/server/virtio>
00015
00016
00021
00033 class Net_transfer
00034 {
00035 public:
00036     virtual ~Net_transfer() = default;
00037
00041     void const *req_id() const { return _req_id; }
00042
00046     virtual void copy_header(Virtio_net::Hdr *dst_header) const = 0;
00047
00054     Buffer &cur_buf() { return _cur_buf; }
00055
00065     virtual bool done() = 0;
00066
00067 protected:
00068     Buffer _cur_buf;
00069     void const *_req_id;
00070 };
00071
00072 class Net_request
00073 {
00074 public:
00075
00076     bool has_vlan() const
00077     {
00078         if (!_pkt.pos || _pkt.left < 14)
00079             return false;
00080
00081         uint8_t *p = reinterpret_cast<uint8_t *>(_pkt.pos);
00082         return p[12] == 0x81U && p[13] == 0x00U;
00083     }
00084
00085     uint16_t vlan_id() const
00086     {
00087         if (!has_vlan() || _pkt.left < 16)
00088             return VLAN_ID_NATIVE;
00089
00090         uint8_t *p = reinterpret_cast<uint8_t *>(_pkt.pos);
00091         return (uint16_t{p[14]} « 8 | p[15]) & 0xffffU;
00092     }
00093
00105     uint8_t const *buffer(size_t *size) const
00106     {
00107         *size = _pkt.left;
00108         return reinterpret_cast<uint8_t const *>(_pkt.pos);
00109     }
00110
00111     void dump_pkt() const
00112     {
00113         Dbg pkt_debug(Dbg::Packet, Dbg::Debug, "PKT");
00114         if (pkt_debug.is_active())
00115         {
00116             //pkt_debug.cprintf("\t");
00117             //src_mac().print(pkt_debug);
00118             //pkt_debug.cprintf(" -> ");
00119             //dst_mac().print(pkt_debug);
00120             //pkt_debug.cprintf("\n");
00121
00122             Dbg pkt_trace(Dbg::Packet, Dbg::Trace, "PKT");
00123             if (pkt_trace.is_active() && _pkt.left >= 14)
00124             {
00125                 uint8_t const *packet = reinterpret_cast<uint8_t const *>(_pkt.pos);
00126                 pkt_trace.cprintf("\n\tEthertype: ");
00127                 uint16_t ether_type = uint16_t{packet[12]} « 8 | packet[13];
00128                 char const *protocol;
00129                 switch (ether_type)
00130                 {
00131                     case 0x0800: protocol = "IPv4"; break;
00132                     case 0x0806: protocol = "ARP"; break;
00133                     case 0x8100: protocol = "Vlan"; break;
00134                     case 0x86dd: protocol = "IPv6"; break;
00135                     case 0x8863: protocol = "PPPoE Discovery"; break;
00136                     case 0x8864: protocol = "PPPoE Session"; break;
00137                     default: protocol = nullptr;
00138                 }
00139                 if (protocol)
00140                     pkt_trace.cprintf("%s\n", protocol);
00141                 else
00142                     pkt_trace.cprintf("%04x\n", ether_type);

```

```

00143     }
00144     }
00145     }
00146
00147 protected:
00148     Buffer _pkt;
00149 };
00150

```

## 16.61 request\_ixl.h

```

00001 /*
00002  * Copyright (C) 2024-2025 Kernkonzept GmbH.
00003  * Author(s): Georg Kotheimer <georg.kotheimer@kernkonzept.com>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007 #pragma once
00008
00009 #include "port.h"
00010 #include "request.h"
00011
00012 #include <14/ixl/memory.h>
00013
00014 #include <utility>
00015
00020
00021 class Ixl_net_request final : public Net_request
00022 {
00023 public:
00024     class Ixl_net_transfer final : public Net_transfer
00025     {
00026     public:
00027         explicit Ixl_net_transfer(Ixl_net_request const &request)
00028             : _request(request)
00029         {
00030             _cur_buf = Buffer(reinterpret_cast<char *>(request.buf()->data),
00031                             request.buf()->size);
00032             _req_id = _request.buf();
00033         }
00034
00035         // delete copy constructor and copy assignment operator
00036         Ixl_net_transfer(Ixl_net_transfer const &) = delete;
00037         Ixl_net_transfer &operator = (Ixl_net_transfer const &) = delete;
00038
00039         void copy_header(Virtio_net::Hdr *dst_header) const override
00040         {
00041             dst_header->flags.data_valid() = 0;
00042             dst_header->flags.need_csum() = 0;
00043             dst_header->gso_type = 0; // GSO_NONE
00044             dst_header->hdr_len = sizeof(Virtio_net::Hdr);
00045             dst_header->gso_size = 0;
00046             dst_header->csum_start = 0;
00047             dst_header->csum_offset = 0;
00048             dst_header->num_buffers = 1;
00049         }
00050
00051         bool done() override { return _cur_buf.done(); }
00052
00053     private:
00054         Ixl_net_request const &_request;
00055     };
00056
00057     void dump_request(Port_iface *port) const
00058     {
00059         Dbg debug(Dbg::Request, Dbg::Debug, "REQ-IXL");
00060         if (debug.is_active())
00061         {
00062             debug.printf("%s: Next packet: %p - %x bytes\n",
00063                         port->get_name(), _pkt.pos, _pkt.left);
00064         }
00065         dump_pkt();
00066     }
00067
00068     explicit Ixl_net_request(Ixl::pkt_buf *buf) : _buf(buf)
00069     {
00070         _pkt = Buffer(reinterpret_cast<char *>(buf->data), buf->size);
00071     }
00072
00073     // delete copy constructor and copy assignment operator
00074     Ixl_net_request(Ixl_net_request const &) = delete;
00075     Ixl_net_request &operator=(Ixl_net_request const &) = delete;
00076

```

```

00077 // define move constructor and copy assignment operator
00078 Ixl_net_request(Ixl_net_request &&other)
00079 : _buf(other._buf)
00080 {
00081     _pkt = std::move(other._pkt);
00082
00083     // Invalidate other.
00084     other._buf = nullptr;
00085 }
00086
00087 Ixl_net_request &operator=(Ixl_net_request &&other)
00088 {
00089     // Invalidate self.
00090     if (_buf != nullptr)
00091         Ixl::pkt_buf_free(_buf);
00092
00093     _buf = other._buf;
00094     _pkt = std::move(other._pkt);
00095
00096     // Invalidate other.
00097     other._buf = nullptr;
00098
00099     return *this;
00100 }
00101
00102 ~Ixl_net_request()
00103 {
00104     if (_buf != nullptr)
00105     {
00106         Ixl::pkt_buf_free(_buf);
00107         _buf = nullptr;
00108     }
00109 }
00110
00112 Mac_addr dst_mac() const
00113 {
00114     return (_pkt.pos && _pkt.left >= Mac_addr::Addr_length)
00115         ? Mac_addr::from_uncached(_pkt.pos)
00116         : Mac_addr(Mac_addr::Addr_unknown);
00117 }
00118
00120 Mac_addr src_mac() const
00121 {
00122     return (_pkt.pos && _pkt.left >= Mac_addr::Addr_length * 2)
00123         ? Mac_addr::from_uncached(_pkt.pos + Mac_addr::Addr_length)
00124         : Mac_addr(Mac_addr::Addr_unknown);
00125 }
00126
00127 Ixl::pkt_buf *buf() const { return _buf; }
00128
00129 Ixl_net_transfer transfer_src() const
00130 { return Ixl_net_transfer(*this); }
00131
00132 private:
00133     Ixl::pkt_buf *_buf;
00134 };
00135

```

## 16.62 request\_l4virtio.h

```

00001 /*
00002  * Copyright (C) 2016-2017, 2020, 2022, 2024-2025 Kernkonzept GmbH.
00003  * Author(s): Jean Wolter <jean.wolter@kernkonzept.com>
00004  *            Georg Kotheimer <georg.kotheimer@kernkonzept.com>
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00008 #pragma once
00009
00010 #include "debug.h"
00011 #include "port.h"
00012 #include "request.h"
00013 #include "virtio_net.h"
00014
00015 #include <l4/l4virtio/server/virtio>
00016 #include <l4/util/assert.h>
00017
00018 #include <optional>
00019 #include <utility>
00020
00025
00035 class Virtio_net_request final : public Net_request
00036 {

```

```

00037 public:
00038     class Virtio_net_transfer final : public Net_transfer
00039     {
00040     public:
00041         explicit Virtio_net_transfer(Virtio_net_request const &request)
00042         : _request(request),
00043           // We already looked at the very first buffer to find the target of the
00044           // packet. The request processor of the "parent request" contains the
00045           // current state of the transaction up to this point. Since there might be
00046           // more than one target for the request we have to keep track of our own
00047           // state and need our own request processor instance, which will be
00048           // initialized using the current state of the "parent request".
00049           _req_proc(_request.get_request_processor())
00050         {
00051             // The buffer descriptors used for this transaction and the amount of bytes
00052             // copied to the current target descriptor.
00053             _cur_buf = request.first_buffer();
00054             _req_id = _request.header();
00055         }
00056
00057         // delete copy constructor and copy assignment operator
00058         Virtio_net_transfer(Virtio_net_transfer const &) = delete;
00059         Virtio_net_transfer &operator = (Virtio_net_transfer const &) = delete;
00060
00061         void copy_header(Virtio_net::Hdr *dst_header) const override
00062         {
00063             memcpy(dst_header, _request.header(), sizeof(Virtio_net::Hdr));
00064         }
00065
00066         bool done() override
00067         {
00068             return _cur_buf.done() && !_req_proc.next(_request.dev()->mem_info(), &_cur_buf);
00069         }
00070
00071     private:
00072         Virtio_net_request const &_request;
00073         L4virtio::Svr::Request_processor _req_proc;
00074     };
00075
00076     void dump_request(Port_iface *port) const
00077     {
00078         Dbg debug(Dbg::Request, Dbg::Debug, "REQ-VIO");
00079         if (debug.is_active())
00080         {
00081             debug.printf("%s: Next packet: %p:%p - %x bytes\n",
00082                         port->get_name(), _header, _pkt.pos, _pkt.left);
00083             if (_header->flags.raw || _header->gso_type)
00084             {
00085                 debug.cprintf("flags:\t%x\n\t"
00086                               "gso_type:\t%x\n\t"
00087                               "header len:\t%x\n\t"
00088                               "gso size:\t%x\n\t"
00089                               "csum start:\t%x\n\t"
00090                               "csum offset:\t%x\n\t"
00091                               "\tnum buffer:\t%x\n\t",
00092                               _header->flags.raw,
00093                               _header->gso_type, _header->hdr_len,
00094                               _header->gso_size,
00095                               _header->csum_start, _header->csum_offset,
00096                               _header->num_buffers);
00097             }
00098         }
00099         dump_pkt();
00100     }
00101
00102     // delete copy constructor and copy assignment operator
00103     Virtio_net_request(Virtio_net_request const &) = delete;
00104     Virtio_net_request &operator = (Virtio_net_request const &) = delete;
00105
00106     // define move constructor and copy assignment operator
00107     Virtio_net_request(Virtio_net_request &&other)
00108     : _dev(other._dev),
00109       _queue(other._queue),
00110       _head(std::move(other._head)),
00111       _req_proc(std::move(other._req_proc)),
00112       _header(other._header)
00113     {
00114         _pkt = std::move(other._pkt);
00115
00116         // Invalidate other.
00117         other._queue = nullptr;
00118     }
00119
00120     Virtio_net_request &operator = (Virtio_net_request &&other)
00121     {
00122         // Invalidate self.
00123         finish();

```



```

00124
00125     _dev = other._dev;
00126     _queue = other._queue;
00127     _head = std::move(other._head);
00128     _req_proc = std::move(other._req_proc);
00129     _header = other._header;
00130     _pkt = std::move(other._pkt);
00131
00132     // Invalidate other.
00133     other._queue = nullptr;
00134
00135     return *this;
00136 }
00137
00138 Virtio_net_request(Virtio_net *dev, L4virtio::Svr::Virtqueue *queue,
00139                   L4virtio::Svr::Virtqueue::Request const &req)
00140 : _dev(dev), _queue(queue)
00141 {
00142     _head = _req_proc.start(_dev->mem_info(), req, &_pkt);
00143
00144     _header = (Virtio_net::Hdr *)_pkt.pos;
00145     l4_uint32_t skipped = _pkt.skip(sizeof(Virtio_net::Hdr));
00146
00147     if (L4_UNLIKELY( (skipped != sizeof(Virtio_net::Hdr))
00148                     || (_pkt.done() && !_next_buffer(&_pkt))))
00149     {
00150         _header = 0;
00151         Dbg(Dbg::Queue, Dbg::Warn).printf("Invalid request\n");
00152         return;
00153     }
00154 }
00155
00156 ~Virtio_net_request()
00157 { finish(); }
00158
00159 bool valid() const
00160 { return _header != 0; }
00161
00172 static void drop_requests(Virtio_net *dev,
00173                           L4virtio::Svr::Virtqueue *queue)
00174 {
00175     if (L4_UNLIKELY(!queue->ready()))
00176         return;
00177
00178     if (queue->desc_avail())
00179         Dbg(Dbg::Request, Dbg::Debug)
00180             .printf("Dropping incoming packets on monitor port\n");
00181
00182     L4virtio::Svr::Request_processor req_proc;
00183     Buffer pkt;
00184
00185     while (auto req = queue->next_avail())
00186     {
00187         auto head = req_proc.start(dev->mem_info(), req, &pkt);
00188         queue->finish(head, dev, 0);
00189     }
00190 }
00191
00198 static std::optional<Virtio_net_request>
00199 get_request(Virtio_net *dev, L4virtio::Svr::Virtqueue *queue)
00200 {
00201     if (L4_UNLIKELY(!queue->ready()))
00202         return std::nullopt;
00203
00204     if (auto r = queue->next_avail())
00205     {
00206         // Virtio_net_request keeps "a lot of internal state",
00207         // therefore we create the object before creating the
00208         // state.
00209         // We might check later on whether it is possible to
00210         // save the state when we actually have to because a
00211         // transfer is blocking on a port.
00212         auto request = Virtio_net_request(dev, queue, r);
00213         if (request.valid())
00214             return request;
00215     }
00216     return std::nullopt;
00217 }
00218
00219 Buffer const &first_buffer() const
00220 { return _pkt; }
00221
00222 Virtio_net::Hdr const *header() const
00223 { return _header; }
00224
00225 L4virtio::Svr::Request_processor const &get_request_processor() const
00226 { return _req_proc; }

```

```

00227
00228 Virtio_net const *dev() const
00229 { return _dev; }
00230
00231 Virtio_net_transfer transfer_src() const
00232 { return Virtio_net_transfer(*this); }
00233
00235 Mac_addr dst_mac() const
00236 {
00237     return (_pkt.pos && _pkt.left >= Mac_addr::Addr_length)
00238         ? Mac_addr(_pkt.pos)
00239         : Mac_addr(Mac_addr::Addr_unknown);
00240 }
00241
00243 Mac_addr src_mac() const
00244 {
00245     return (_pkt.pos && _pkt.left >= Mac_addr::Addr_length * 2)
00246         ? Mac_addr(_pkt.pos + Mac_addr::Addr_length)
00247         : Mac_addr(Mac_addr::Addr_unknown);
00248 }
00249
00250
00251 private:
00252     /* needed for Virtqueue::finish() */
00253     Virtio_net *_dev;
00254     L4virtio::Svr::Virtqueue *_queue;
00255     L4virtio::Svr::Virtqueue::Head_desc _head;
00256
00257     /* the actual request processor, encapsulates the decoding of the request */
00258     L4virtio::Svr::Request_processor _req_proc;
00259
00260     /* A request to the virtio net layer consists of one or more buffers
00261        containing the Virtio_net::Hdr and the actual packet. To make a
00262        switching decision we need to be able to look at the packet while
00263        still being able access the Virtio_net::Hdr for the actual copy
00264        operation. Therefore we keep track of two locations, the header
00265        location and the start of the packet (which might be in a
00266        different buffer) */
00267     Virtio_net::Hdr *_header;
00268
00269     bool _next_buffer(Buffer *buf)
00270     { return _req_proc.next(_dev->mem_info(), buf); }
00271
00272     void finish()
00273     {
00274         if (_queue == nullptr || !_queue->ready())
00275             return;
00276
00277         Dbg(Dbg::Virtio, Dbg::Trace).printf("%s(%p)\n", __PRETTY_FUNCTION__, this);
00278         _queue->finish(_head, _dev, 0);
00279         _queue = nullptr;
00280     }
00281 };
00282
00283
00284
00285
00286
00287
00288
00289
00290

```

## 16.63 stats.h

```

00001 #include <l4/re/env>
00002 #include <l4/re/dataspace>
00003 #include <l4/re/error_helper>
00004 #include <l4/re/util/cap_alloc>
00005 #include <l4/virtio-net-switch/stats.h>
00006
00007 class Switch_statistics
00008 {
00009 private:
00010     L4Re::Util::Ref_cap<L4Re::Dataspace>::Cap _ds;
00011     Virtio_net_switch::Statistics *_stats;
00012     bool _initialized = false;
00013
00014     Switch_statistics() {}
00015
00016     ~Switch_statistics()
00017     {
00018         if (_initialized)
00019             L4Re::Env::env()->rm()->detach(reinterpret_cast<l4_addr_t>(_stats), 0);
00020     }
00021
00022     l4_size_t _size;
00023
00024 public:
00025     Virtio_net_switch::Statistics *stats()
00026     {

```

```

00027     if (!_initialized)
00028         return _stats;
00029     else
00030         throw L4::Runtime_error(-L4_EAGAIN, "Statistics not set up.");
00031 }
00032
00033 static Switch_statistics& get_instance()
00034 {
00035     static Switch_statistics instance;
00036     return instance;
00037 }
00038
00039 void initialize(l4_uint64_t num_max_ports)
00040 {
00041     _size = l4_round_page(sizeof(Virtio_net_switch::Statistics)
00042         + sizeof(Virtio_net_switch::Port_statistics) * num_max_ports);
00043     void *addr = malloc(_size);
00044     if (!addr)
00045         throw L4::Runtime_error(-L4_ENOMEM,
00046             "Could not allocate statistics memory.");
00047
00048     memset(addr, 0, _size);
00049     _stats = reinterpret_cast<Virtio_net_switch::Statistics *>(addr);
00050     _initialized = true;
00051     _stats->max_ports = num_max_ports;
00052 }
00053
00054 Virtio_net_switch::Port_statistics *
00055 allocate_port_statistics(char const* name)
00056 {
00057     for (unsigned i = 0; i < _stats->max_ports; ++i)
00058     {
00059         if (!_stats->port_stats[i].in_use)
00060         {
00061             memset(reinterpret_cast<void*>(&_stats->port_stats[i]), 0,
00062                 sizeof(Virtio_net_switch::Port_statistics));
00063             _stats->port_stats[i].in_use = 1;
00064             size_t len = std::min(strlen(name), sizeof(_stats->port_stats[i].name) - 1);
00065             memcpy(_stats->port_stats[i].name, name, len);
00066             _stats->port_stats[i].name[len] = '\0';
00067             _stats->age++;
00068             return &_stats->port_stats[i];
00069         }
00070     }
00071     return nullptr;
00072 }
00073
00074 inline l4_size_t size()
00075 { return _size; }
00076
00077 Switch_statistics(Switch_statistics const&) = delete;
00078 void operator=(Switch_statistics const &) = delete;
00079 };

```

## 16.64 switch.cc

```

00001 /*
00002  * Copyright (C) 2016-2018, 2020, 2023-2025 Kernkonzept GmbH.
00003  * Author(s): Jean Wolter <jean.wolter@kernkonzept.com>
00004  *            Alexander Warg <warg@os.inf.tu-dresden.de>
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00008 #include "debug.h"
00009 #include "switch.h"
00010 #include "filter.h"
00011
00012 Virtio_switch::Virtio_switch(unsigned max_ports)
00013 : _max_ports(max_ports)
00014 {}
00015
00016 bool
00017 Virtio_switch::add_port(Port_iface *port)
00018 {
00019     if (_ports.size() == _max_ports)
00020     {
00021         Dbg(Dbg::Port, Dbg::Warn)
00022             .printf("Port limit (%u) has been reached.\n", _max_ports);
00023         return false;
00024     }
00025
00026     if (!port->mac().is_unknown())
00027         for (auto const *p: _ports)

```

```

00028         if (p->mac() == port->mac())
00029         {
00030             Dbg(Dbg::Port, Dbg::Warn)
00031                 .printf("Rejecting port '%s'. MAC address already in use.\n",
00032                     port->get_name());
00033             return false;
00034         }
00035     }
00036     _ports.push_back(port);
00037     return true;
00038 }
00039
00040 bool
00041 Virtio_switch::add_monitor_port(Port_iface *port)
00042 {
00043     if (!_monitor)
00044     {
00045         _monitor = port;
00046         return true;
00047     }
00048     Dbg(Dbg::Port, Dbg::Warn).printf("'%' already defined as monitor port,"
00049         " rejecting monitor port '%s'\n",
00050         _monitor->get_name(), port->get_name());
00051     return false;
00052 }
00053
00054 void
00055 Virtio_switch::check_ports()
00056 {
00057     for (std::vector<Port_iface *>::iterator it = _ports.begin();
00058          it != _ports.end(); )
00059     {
00060         auto *port = *it;
00061         if (port->is_gone())
00062         {
00063             Dbg(Dbg::Port, Dbg::Info)
00064                 .printf("Client on port %p has gone. Deleting...\n", port);
00065             _mac_table.flush(port);
00066             it = _ports.erase(it);
00067             delete port;
00068         }
00069         else
00070             ++it;
00071     }
00072     if (_monitor && _monitor->is_gone())
00073     {
00074         delete(_monitor);
00075         _monitor = nullptr;
00076     }
00077 }
00078
00079 template<typename REQ>
00080 void
00081 Virtio_switch::handle_tx_request(Port_iface *port, REQ const &request)
00082 {
00083     // Trunk ports are required to have a VLAN tag and only accept packets that
00084     // belong to a configured VLAN.
00085     if (port->is_trunk() && !port->match_vlan(request.vlan_id()))
00086     {
00087         // Drop packet.
00088         port->stat_inc_tx_dropped();
00089         return;
00090     }
00091     // Access ports must not be VLAN tagged to prevent double tagging attacks.
00092     if (port->is_access() && request.has_vlan())
00093     {
00094         // Drop packet.
00095         port->stat_inc_tx_dropped();
00096         return;
00097     }
00098     auto handle_request = [](Port_iface *dst_port, Port_iface *src_port,
00099                             REQ const &req)
00100     {
00101         auto transfer_src = req.transfer_src();
00102         l4_uint64_t bytes;
00103         auto res = dst_port->handle_request(src_port, transfer_src, &bytes);
00104         switch (res)
00105         {
00106             case Port_iface::Result::Delivered:
00107                 dst_port->stat_inc_tx_num();
00108                 dst_port->stat_inc_tx_bytes(bytes);
00109                 src_port->stat_inc_rx_num();

```

```

00115         src_port->stat_inc_rx_bytes(bytes);
00116         break;
00117     case Port_iface::Result::Dropped:
00118         [[fallthrough]];
00119     case Port_iface::Result::Exception:
00120         [[fallthrough]];
00121     default:
00122         dst_port->stat_inc_tx_dropped();
00123         break;
00124     }
00125 };
00126
00127 Mac_addr src = request.src_mac();
00128
00129 auto dst = request.dst_mac();
00130 bool is_broadcast = dst.is_broadcast();
00131 uint16_t vlan = request.has_vlan() ? request.vlan_id() : port->get_vlan();
00132 _mac_table.learn(src, port, vlan);
00133 if (L4_LIKELY(!is_broadcast))
00134 {
00135     auto *target = _mac_table.lookup(dst, vlan);
00136     if (target)
00137     {
00138         // Do not send packets to the port they came in; they might
00139         // be sent to us by another switch which does not know how
00140         // to reach the target.
00141         if (target != port)
00142         {
00143             handle_request(target, port, request);
00144             if (_monitor && !filter_request(request))
00145                 handle_request(_monitor, port, request);
00146         }
00147         return;
00148     }
00149 }
00150
00151 // It is either a broadcast or an unknown destination - send to all
00152 // known ports except the source port
00153 for (auto *target: _ports)
00154 {
00155     if (target != port && target->match_vlan(vlan))
00156         handle_request(target, port, request);
00157 }
00158
00159 // Send a copy to the monitor port
00160 if (_monitor && !filter_request(request))
00161     handle_request(_monitor, port, request);
00162 }
00163
00164 template<typename PORT>
00165 void
00166 Virtio_switch::handle_tx_requests(PORT *port, unsigned &num_reqs_handled)
00167 {
00168     while (auto req = port->get_tx_request())
00169     {
00170         req->dump_request(port);
00171         handle_tx_request(port, *req);
00172
00173         if (++num_reqs_handled >= Tx_burst)
00174             // Port has hit its TX burst limit.
00175             break;
00176     }
00177 }
00178
00179 bool
00180 Virtio_switch::handle_l4virtio_port_tx(L4virtio_port *port)
00181 {
00182     /* handle IRQ on one port for the time being */
00183     if (!port->tx_work_pending())
00184         Dbg(Dbg::Port, Dbg::Debug)
00185             .printf("%s: Irq without pending work\n", port->get_name());
00186
00187     unsigned num_reqs_handled = 0;
00188     do
00189     {
00190         port->tx_q()->disable_notify();
00191         port->rx_q()->disable_notify();
00192
00193         if (num_reqs_handled >= Tx_burst)
00194         {
00195             Dbg(Dbg::Port, Dbg::Debug)
00196                 .printf(
00197                     "%s: Tx burst limit hit, reschedule remaining Tx work.\n",
00198                     port->get_name());
00199
00200             // Port has hit its TX burst limit, so for fairness reasons, stop
00201             // processing TX work from this port, and instead reschedule the

```

```

00202         // pending work for later.
00203         port->reschedule_pending_tx();
00204         // NOTE: Notifications for this port remain disabled, until eventually
00205         // the reschedule handler calls 'handle_l4virtio_port_tx' again.
00206         return false;
00207     }
00208
00209     // Within the loop, to trigger before enabling notifications again.
00210     all_rx_notify_disable_and_remember();
00211
00212     try
00213     {
00214         // throws Bad_descriptor exceptions raised on SRC port
00215         handle_tx_requests(port, num_reqs_handled);
00216     }
00217     catch (L4virtio::Svr::Bad_descriptor &e)
00218     {
00219         Dbg(Dbg::Port, Dbg::Warn, "REQ")
00220             .printf("%s: caught bad descriptor exception: %s - %i"
00221                 " -- Signal device error on device %p.\n",
00222                 __PRETTY_FUNCTION__, e.message(), e.error, port);
00223         port->device_error();
00224         all_rx_notify_emit_and_enable();
00225         return false;
00226     }
00227
00228     all_rx_notify_emit_and_enable();
00229
00230     port->tx_q()->enable_notify();
00231     port->rx_q()->enable_notify();
00232
00233     L4virtio::wmb();
00234     L4virtio::rmb();
00235 }
00236 while (port->tx_work_pending());
00237
00238 return true;
00239 }
00240
00241 #if CONFIG_VNS_IXL
00242 bool
00243 Virtio_switch::handle_ixl_port_tx(Ixl_port *port)
00244 {
00245     unsigned num_reqs_handled = 0;
00246
00247     all_rx_notify_disable_and_remember();
00248     handle_tx_requests(port, num_reqs_handled);
00249     all_rx_notify_emit_and_enable();
00250
00251     if (num_reqs_handled >= Tx_burst && port->tx_work_pending())
00252     {
00253         Dbg(Dbg::Port, Dbg::Info)
00254             .printf("%s: Tx burst limit hit, reschedule remaining Tx work.\n",
00255                 port->get_name());
00256
00257         // Port has hit its TX burst limit, so for fairness reasons, stop
00258         // processing TX work from this port, and instead reschedule the
00259         // pending work for later.
00260         port->reschedule_pending_tx();
00261         return false;
00262     }
00263
00264     return true;
00265 }
00266 #endif
00267

```

## 16.65 switch.h

```

00001 /*
00002  * Copyright (C) 2016-2017, 2020, 2022-2025 Kernkonzept GmbH.
00003  * Author(s): Jean Wolter <jean.wolter@kernkonzept.com>
00004  *             Alexander Warg <warg@os.inf.tu-dresden.de>
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00008 #pragma once
00009
00010 #include "port.h"
00011 #include "port_l4virtio.h"
00012 #include "mac_table.h"
00013
00014 #if CONFIG_VNS_IXL

```

```

00015 #include "port_ixl.h"
00016 #endif
00017
00018 #include <vector>
00019
00035 class Virtio_switch
00036 {
00037 private:
00038     std::vector<Port_iface *> _ports;
00039     Port_iface *_monitor = nullptr;
00040
00041     unsigned _max_ports;
00042     Mac_table<> _mac_table;
00043
00044     // Limits the number of consecutive TX requests a port can process before
00045     // being interrupted to ensure fairness to other ports.
00046     static constexpr unsigned Tx_burst = 128;
00047
00057     template<typename REQ>
00058     void handle_tx_request(Port_iface *port, REQ const &request);
00059
00060     template<typename PORT>
00061     void handle_tx_requests(PORT *port, unsigned &num_reqs_handled);
00062
00063
00064     void all_rx_notify_emit_and_enable()
00065     {
00066         for (auto *port : _ports)
00067             port->rx_notify_emit_and_enable();
00068     }
00069
00070     void all_rx_notify_disable_and_remember()
00071     {
00072         for (auto *port: _ports)
00073             port->rx_notify_disable_and_remember();
00074     }
00075
00076 public:
00083     explicit Virtio_switch(unsigned max_ports);
00084
00093     bool add_port(Port_iface *port);
00094
00103     bool add_monitor_port(Port_iface *port);
00104
00112     void check_ports();
00113
00123     bool handle_l4virtio_port_tx(L4virtio_port *port);
00124
00125 #if CONFIG_VNS_IXL
00135     bool handle_ixl_port_tx(Ixl_port *port);
00136 #endif
00137
00146     bool port_available(bool monitor)
00147     {
00148         if (monitor)
00149             return _monitor == 0;
00150
00151         return _ports.size() < _max_ports;
00152     }
00153 };

```

## 16.66 virtio\_net.h

```

00001 /*
00002  * Copyright (C) 2016-2017, 2019, 2022-2025 Kernkonzept GmbH.
00003  * Author(s): Jean Wolter <jean.wolter@kernkonzept.com>
00004  *             Alexander Warg <warg@os.inf.tu-dresden.de>
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00008 #pragma once
00009
00010 #include <l4/re/dataspace>
00011 #include <l4/re/util/unique_cap>
00012
00013 #include <l4/sys/cxx/ipc_epiface>
00014
00015 #include <l4/l4virtio/server/virtio>
00016 #include <l4/l4virtio/server/l4virtio>
00017 #include <l4/l4virtio/l4virtio>
00018
00019 #include "debug.h"
00024 class Virtqueue : public L4virtio::Svr::Virtqueue

```

```

00025 {
00026 public:
00027     bool kick_queue()
00028     {
00029         if (no_notify_guest())
00030             return false;
00031
00032         if (_do_kick)
00033             return true;
00034
00035         _kick_pending = true;
00036         return false;
00037     }
00038
00039     bool kick_enable_get_pending()
00040     {
00041         _do_kick = true;
00042         return _kick_pending;
00043     }
00044
00045     void kick_disable_and_remember()
00046     {
00047         _do_kick = false;
00048         _kick_pending = false;
00049     }
00050
00051 private:
00052     bool _do_kick = true;
00053     bool _kick_pending = false;
00054 };
00055
00071 class Virtio_net :
00072     public L4virtio::Svr::Device,
00073     public L4::Epiface_t<Virtio_net, L4virtio::Device>
00074 {
00075 public:
00076     struct Hdr_flags
00077     {
00078         l4_uint8_t raw;
00079         CXX_BITFIELD_MEMBER( 0, 0, need_csum, raw);
00080         CXX_BITFIELD_MEMBER( 1, 1, data_valid, raw);
00081     };
00082
00083     struct Hdr
00084     {
00085         Hdr_flags flags;
00086         l4_uint8_t gso_type;
00087         l4_uint16_t hdr_len;
00088         l4_uint16_t gso_size;
00089         l4_uint16_t csum_start;
00090         l4_uint16_t csum_offset;
00091         l4_uint16_t num_buffers;
00092     };
00093
00094     struct Features : L4virtio::Svr::Dev_config::Features
00095     {
00096         Features() = default;
00097         Features(l4_uint32_t raw) : L4virtio::Svr::Dev_config::Features(raw) {}
00098
00099         CXX_BITFIELD_MEMBER( 0, 0, csum, raw); // host handles partial csum
00100         CXX_BITFIELD_MEMBER( 1, 1, guest_csum, raw); // guest handles partial csum
00101         CXX_BITFIELD_MEMBER( 5, 5, mac, raw); // host has given mac
00102         CXX_BITFIELD_MEMBER( 6, 6, gso, raw); // host handles packets /w any GSO
00103         CXX_BITFIELD_MEMBER( 7, 7, guest_tso4, raw); // guest handles TSOv4 in
00104         CXX_BITFIELD_MEMBER( 8, 8, guest_tso6, raw); // guest handles TSOv6 in
00105         CXX_BITFIELD_MEMBER( 9, 9, guest_ecn, raw); // guest handles TSO[6] with ECN in
00106         CXX_BITFIELD_MEMBER(10, 10, guest_ufo, raw); // guest handles UFO in
00107         CXX_BITFIELD_MEMBER(11, 11, host_tso4, raw); // host handles TSOv4 in
00108         CXX_BITFIELD_MEMBER(12, 12, host_tso6, raw); // host handles TSOv6 in
00109         CXX_BITFIELD_MEMBER(13, 13, host_ecn, raw); // host handles TSO[6] with ECN in
00110         CXX_BITFIELD_MEMBER(14, 14, host_ufo, raw); // host handles UFO
00111         CXX_BITFIELD_MEMBER(15, 15, mrg_rxbuf, raw); // host can merge receive buffers
00112         CXX_BITFIELD_MEMBER(16, 16, status, raw); // virtio_net_config.status available
00113         CXX_BITFIELD_MEMBER(17, 17, ctrl_vq, raw); // Control channel available
00114         CXX_BITFIELD_MEMBER(18, 18, ctrl_rx, raw); // Control channel RX mode support
00115         CXX_BITFIELD_MEMBER(19, 19, ctrl_vlan, raw); // Control channel VLAN filtering
00116         CXX_BITFIELD_MEMBER(20, 20, ctrl_rx_extra, raw); // Extra RX mode control support
00117         CXX_BITFIELD_MEMBER(21, 21, guest_announce, raw); // Guest can announce device on the network
00118         CXX_BITFIELD_MEMBER(22, 22, mq, raw); // Device supports Receive Flow Steering
00119         CXX_BITFIELD_MEMBER(23, 23, ctrl_mac_addr, raw); // Set MAC address
00120     };
00121
00122     enum
00123     {
00124         Rx = 0,
00125         Tx = 1,
00126     };

```



```

00127
00128 struct Net_config_space
00129 {
00130     // The config defining mac address (if VIRTIO_NET_F_MAC aka Features::mac)
00131     l4_uint8_t mac[6];
00132     // currently not used ...
00133     l4_uint16_t status;
00134     l4_uint16_t max_virtqueue_pairs;
00135 };
00136
00137 L4virtio::Svr::Dev_config_t<Net_config_space> _dev_config;
00138
00139 explicit Virtio_net(unsigned vq_max)
00140 : L4virtio::Svr::Device(&_dev_config),
00141   _dev_config(L4VIRTIO_VENDOR_KK, L4VIRTIO_ID_NET, 2),
00142   _vq_max(vq_max)
00143 {
00144     Features hf(0);
00145     hf.ring_indirect_desc() = true;
00146     hf.mrg_rxbuf() = true;
00147 #if 0
00148     // disable currently unsupported options, but leave them in for
00149     // documentation purposes
00150     hf.csum() = true;
00151     hf.host_tso4() = true;
00152     hf.host_tso6() = true;
00153     hf.host_ufo() = true;
00154     hf.host_ecn() = true;
00155
00156     hf.guest_csum() = true;
00157     hf.guest_tso4() = true;
00158     hf.guest_tso6() = true;
00159     hf.guest_ufo() = true;
00160     hf.guest_ecn() = true;
00161 #endif
00162
00163     _dev_config.host_features(0) = hf.raw;
00164     _dev_config.set_host_feature(L4VIRTIO_FEATURE_VERSION_1);
00165     _dev_config.reset_hdr();
00166
00167     reset_queue_config(Rx, vq_max);
00168     reset_queue_config(Tx, vq_max);
00169 }
00170
00171 void reset() override
00172 {
00173     for (L4virtio::Svr::Virtqueue &q: _q)
00174         q.disable();
00175
00176     reset_queue_config(Rx, _vq_max);
00177     reset_queue_config(Tx, _vq_max);
00178     _dev_config.reset_hdr();
00179 }
00180
00181 template<typename T, unsigned N >
00182 static unsigned array_length(T (&)[N]) { return N; }
00183
00184 int reconfig_queue(unsigned index) override
00185 {
00186     Dbg(Dbg::Virtio, Dbg::Info, "Virtio")
00187         .printf("(%p): Reconfigure queue %d (%p): Status: %02x\n",
00188             this, index, _q + index, _dev_config.status().raw);
00189
00190     if (index >= array_length(_q))
00191         return -L4_ERANGE;
00192
00193     if (setup_queue(_q + index, index, _vq_max))
00194         return 0;
00195
00196     return -L4_EINVAL;
00197 }
00198
00199 void dump_features(Dbg const &dbg, const volatile l4_uint32_t *p)
00200 {
00201     dbg.cprintf("%08x:%08x:%08x:%08x:%08x:%08x:%08x\n",
00202         p[0], p[1], p[2], p[3], p[4], p[5], p[6], p[17]);
00203 }
00204
00205 void dump_features()
00206 {
00207     Dbg info(Dbg::Virtio, Dbg::Info, "Virtio");
00208     if (!info.is_active())
00209         return;
00210
00211     auto *hdr = _dev_config.hdr();
00212
00213     info.printf("Device %p running (%02x)\n\thost features: ",

```

```

00214         this, _dev_config.status().raw);
00215     dump_features(info, hdr->dev_features_map);
00216     info.printf("\tquest features: ");
00217     dump_features(info, hdr->driver_features_map);
00218 }
00219
00220 bool check_features() override
00221 {
00222     _negotiated_features = _dev_config.negotiated_features();
00223     return true;
00224 }
00225
00226 bool device_needs_reset() const
00227 { return _dev_config.status().device_needs_reset(); }
00228
00230 bool check_queues() override
00231 {
00232     for (L4virtio::Svr::Virtqueue &q: _q)
00233         if (!q.ready())
00234             {
00235                 reset();
00236                 Err().printf("failed to start queues\n");
00237                 return false;
00238             }
00239     dump_features();
00240     return true;
00241 }
00242
00243 Server_iface *server_iface() const override
00244 { return L4::Epiface::server_iface(); }
00245
00250 void register_single_driver_irq() override
00251 {
00252     _kick_guest_irq = L4Re::Util::Unique_cap<L4::Irq>(
00253         L4Re::chkcapi(server_iface()->template rcv_cap<L4::Irq>(0)));
00254     L4Re::chksys(server_iface()->realloc_rcv_cap(0));
00255 }
00256
00257 void trigger_driver_config_irq() override
00258 {
00259     _dev_config.add_irq_status(L4VIRTIO_IRQ_STATUS_CONFIG);
00260     _kick_guest_irq->trigger();
00261 }
00262
00269 void notify_queue(L4virtio::Svr::Virtqueue *queue)
00270 {
00271     // Downcast to Virtqueue to access kick_queue() - we know that our
00272     // queues have the type Virtqueue.
00273     Virtqueue *q = static_cast<Virtqueue*>(queue);
00274     if (q->kick_queue())
00275     {
00276         _dev_config.add_irq_status(L4VIRTIO_IRQ_STATUS_VRING);
00277         _kick_guest_irq->trigger();
00278     }
00279 }
00280
00281 void kick_emit_and_enable()
00282 {
00283     bool kick_pending = false;
00284
00285     for (auto &q : _q)
00286         kick_pending |= q.kick_enable_get_pending();
00287
00288     if (kick_pending)
00289     {
00290         _dev_config.add_irq_status(L4VIRTIO_IRQ_STATUS_VRING);
00291         _kick_guest_irq->trigger();
00292     }
00293 }
00294
00295 void kick_disable_and_remember()
00296 {
00297     for (auto &q : _q)
00298         q.kick_disable_and_remember();
00299 }
00300
00301 Features negotiated_features() const
00302 { return _negotiated_features; }
00303
00305 Virtqueue *tx_q() { return &q[Tx]; }
00307 Virtqueue *rx_q() { return &q[Rx]; }
00309 Virtqueue const *tx_q() const { return &q[Tx]; }
00311 Virtqueue const *rx_q() const { return &q[Rx]; }
00312
00313 private:
00314     Features _negotiated_features;
00316     unsigned _vq_max;

```

```

00318     Virtqueue _q[2];
00323     L4Re::Util::Unique_cap<L4::Irq> _kick_guest_irq;
00324 };

```

## 16.67 virtio\_net.h

```

00001 /* SPDX-License-Identifier: MIT */
00002 /*
00003  * Copyright (C) 2022, 2024 Kernkonzept GmbH.
00004  * Author(s): Stephan Gerhold <stephan.gerhold@kernkonzept.com>
00005  */
00006
00007 #pragma once
00008
00014
00015 #include <l4/sys/types.h>
00016
00020 typedef struct l4virtio_net_header_t
00021 {
00022     l4_uint8_t flags;
00023     l4_uint8_t gso_type;
00024     l4_uint16_t hdr_len;
00025     l4_uint16_t gso_size;
00026     l4_uint16_t csum_start;
00027     l4_uint16_t csum_offset;
00028     l4_uint16_t num_buffers;
00029 } l4virtio_net_header_t;
00030
00034 typedef struct l4virtio_net_config_t
00035 {
00036     l4_uint8_t mac[6];
00037     l4_uint16_t status;
00038     l4_uint16_t max_virtqueue_pairs;
00039     l4_uint16_t mtu;
00040     l4_uint32_t speed;
00041     l4_uint8_t duplex;
00042 } l4virtio_net_config_t;
00043
00045 enum L4virtio_net_feature_bits
00046 {
00047     L4VIRTIO_NET_F_CSUM = 0,
00048     L4VIRTIO_NET_F_GUEST_CSUM = 1,
00049     L4VIRTIO_NET_F_MTU = 3,
00050     L4VIRTIO_NET_F_MAC = 5,
00051     L4VIRTIO_NET_F_GUEST_TSO4 = 7,
00052     L4VIRTIO_NET_F_GUEST_TSO6 = 8,
00053     L4VIRTIO_NET_F_GUEST_ECN = 9,
00054     L4VIRTIO_NET_F_GUEST_UFO = 10,
00055     L4VIRTIO_NET_F_HOST_TSO4 = 11,
00056     L4VIRTIO_NET_F_HOST_TSO6 = 12,
00057     L4VIRTIO_NET_F_HOST_ECN = 13,
00058     L4VIRTIO_NET_F_HOST_UFO = 14,
00059     L4VIRTIO_NET_F_MRG_RXBUF = 15,
00060     L4VIRTIO_NET_F_STATUS = 16,
00061     L4VIRTIO_NET_F_CTRL_VQ = 17,
00062     L4VIRTIO_NET_F_CTRL_RX = 18,
00063     L4VIRTIO_NET_F_CTRL_VLAN = 19,
00064     L4VIRTIO_NET_F_GUEST_ANNOUNCE = 21,
00065     L4VIRTIO_NET_F_MQ = 22,
00066     L4VIRTIO_NET_F_CTRL_MAC_ADDR = 23,
00067 };
00068

```

## 16.68 virtio\_net\_buffer.h

```

00001 /*
00002  * Copyright (C) 2016-2017, 2022, 2024-2025 Kernkonzept GmbH.
00003  * Author(s): Jean Wolter <jean.wolter@kernkonzept.com>
00004  *             Alexander Warg <warg@os.inf.tu-dresden.de>
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00008 #pragma once
00009
00010 #include <l4/l4virtio/server/l4virtio>
00015
00019 struct Buffer : L4virtio::Svr::Data_buffer
00020 {

```

```

00021     Buffer() = default;
00022     Buffer(L4virtio::Svr::Driver_mem_region const *r,
00023           L4virtio::Svr::Virtqueue::Desc const &d,
00024           L4virtio::Svr::Request_processor const *)
00025     {
00026         pos = static_cast<char *>(r->local(d.addr));
00027         left = d.len;
00028     }
00029
00030     Buffer(char *data, l4_uint32_t size)
00031     {
00032         pos = data;
00033         left = size;
00034     }
00035
00036     template<typename T>
00037     explicit Buffer(T *p) : Data_buffer(p) {};
00038 };
00039

```

## 16.69 vlan.h

```

00001  /*
00002   * Copyright (C) 2020, 2022-2024 Kernkonzept GmbH.
00003   * Author(s): Jan Klötzke <jan.kloetzke@kernkonzept.com>
00004   *
00005   * License: see LICENSE.spdx (in this directory or the directories above)
00006   */
00007  #pragma once
00008
00009  #include <l4/cxx/minmax>
00010  #include <l4/l4virtio/server/virtio>
00011  #include <l4/sys/types.h>
00012  #include <string.h>
00013
00014  #include "virtio_net.h"
00015  #include "virtio_net_buffer.h"
00016
00017  namespace {
00018
00019      const l4_uint16_t VLAN_ID_NATIVE = 0xffffU;
00020      const l4_uint16_t VLAN_ID_TRUNK = 0xfffeU;
00021
00022      inline bool vlan_valid_id(l4_uint16_t id)
00023      {
00024          return id > 0U && id < 0xffffU;
00025      }
00026
00027  }
00028
00029  class Virtio_vlan_mangle
00030  {
00031  public:
00032      l4_uint16_t _tci;
00033      l4_uint8_t _mac_remaining;
00034      l4_int8_t _tag_remaining;
00035
00036      constexpr Virtio_vlan_mangle(l4_uint16_t tci, l4_int8_t tag_remaining)
00037      : _tci{tci}, _mac_remaining{12}, _tag_remaining{tag_remaining}
00038      {}
00039
00040      public:
00041      Virtio_vlan_mangle()
00042      : _tci{0}, _mac_remaining{0}, _tag_remaining{0}
00043      {}
00044
00045      static constexpr Virtio_vlan_mangle add(l4_uint16_t tci)
00046      {
00047          return Virtio_vlan_mangle(tci, 4);
00048      }
00049
00050      static constexpr Virtio_vlan_mangle remove()
00051      {
00052          return Virtio_vlan_mangle(0xffffU, -4);
00053      }
00054
00055      l4_uint32_t copy_pkt(Buffer &dst, Buffer &src)
00056      {
00057          l4_uint32_t ret;
00058
00059          if (L4_LIKELY(_tci == 0))
00060          {
00061              // pass through (no tag or keep tag)
00062              ret = src.copy_to(&dst);
00063          }
00064      }
00065  }
00066

```

```

00101     }
00102     else if (_mac_remaining)
00103     {
00104         // copy initial MAC addresses
00105         ret = src.copy_to(&dst, _mac_remaining);
00106         _mac_remaining -= ret;
00107     }
00108     else if (_tag_remaining > 0)
00109     {
00110         // add VLAN tag
00111         l4_uint8_t tag[4] = {
00112             0x81, 0x00,
00113             static_cast<l4_uint8_t>(_tci >> 8),
00114             static_cast<l4_uint8_t>(_tci & 0xffU)
00115         };
00116         ret = cxx::min(static_cast<l4_uint32_t>(_tag_remaining), dst.left);
00117         memcpy(dst.pos, &tag[4 - _tag_remaining], ret);
00118         dst.skip(ret);
00119         _tag_remaining -= (int)ret;
00120     }
00121     else if (_tag_remaining < 0)
00122     {
00123         // remove VLAN tag
00124         _tag_remaining += static_cast<int>(src.skip(-_tag_remaining));
00125         ret = 0;
00126     }
00127     else
00128     {
00129         ret = src.copy_to(&dst);
00130     }
00131     return ret;
00132 }
00133
00142 void rewrite_hdr(Virtio_net::Hdr *hdr)
00143 {
00144     if (L4_UNLIKELY(_tci != 0 && hdr->flags.need_csum()))
00145     {
00146         if (_tci == 0xffffU)
00147             hdr->csum_start -= 4U;
00148         else
00149             hdr->csum_start += 4U;
00150     }
00151 }
00152 };
00153

```

## 16.70 amd64/l4/sys/segment.h File Reference


Segment handling (AMD64).

```

#include <l4/sys/ipc.h>
#include <l4/sys/task.h>
#include <l4/sys/thread.h>
#include <l4/sys/compiler.h>

```

Include dependency graph for segment.h:



## Enumerations

- enum `L4_task_ldt_x86_consts` { `L4_TASK_LDT_X86_ENTRY_SIZE` = 8 , `L4_TASK_LDT_X86_MAX_ENTRIES` }

*Constants for LDT handling.*

- enum `L4_sys_segment` { `L4_AMD64_SEGMENT_FS` = 0 , `L4_AMD64_SEGMENT_GS` = 1 }

*Constants for identifying segments.*

## Functions

- long `fiasco_ldt_set` (`l4_cap_idx_t` task, void \*ldt, unsigned int num\_desc, unsigned int entry\_number\_start, `l4_utcb_t` \*utcb)

*Set LDT segments descriptors.*

- long `fiasco_gdt_set` (`l4_cap_idx_t` thread, void \*desc, unsigned int size, unsigned int entry\_number\_start, `l4_utcb_t` \*utcb)

*Set GDT segment descriptors.*

- unsigned `fiasco_gdt_get_entry_offset` (`l4_cap_idx_t` thread, `l4_utcb_t` \*utcb)

*Return the offset of the entry in the GDT.*

- long `fiasco_amd64_set_fs` (`l4_cap_idx_t` thread, `l4_umword_t` base, `l4_utcb_t` \*utcb)

*Set the base address for the FS segment.*

- long `fiasco_amd64_set_segment_base` (`l4_cap_idx_t` thread, enum `L4_sys_segment` segr, `l4_umword_t` base, `l4_utcb_t` \*utcb)

*Set the base address for a segment.*

- long `fiasco_amd64_segment_info` (`l4_cap_idx_t` thread, unsigned \*user\_ds, unsigned \*user\_cs, unsigned \*user32\_cs, `l4_utcb_t` \*utcb)

*Get segment information.*

## 16.70.1 Detailed Description

Segment handling (AMD64).

Definition in file [segment.h](#).

## 16.70.2 Enumeration Type Documentation

### 16.70.2.1 L4\_sys\_segment

```
enum L4_sys_segment
```

Constants for identifying segments.

#### Enumerator

L4_AMD64_SEGMENT_FS	Constant identifying the FS segment.
L4_AMD64_SEGMENT_GS	Constant identifying the GS segment.

Definition at line 106 of file [segment.h](#).

### 16.70.2.2 L4\_task\_ldt\_x86\_consts

```
enum L4_task_ldt_x86_consts
```

Constants for LDT handling.

#### Enumerator

L4_TASK_LDT_X86_ENTRY_SIZE	Size of an LDT entry.
L4_TASK_LDT_X86_MAX_ENTRIES	Maximum number of LDT entries that can be written with one call.

Definition at line 75 of file [segment.h](#).

## 16.70.3 Function Documentation

### 16.70.3.1 fiasco\_amd64\_segment\_info()

```
long fiasco_amd64_segment_info (  
    l4_cap_idx_t thread,  
    unsigned * user_ds,  
    unsigned * user_cs,  
    unsigned * user32_cs,  
    l4_utcb_t * utcb) [inline]
```

Get segment information.

**Parameters**

in	<i>thread</i>	Thread to get info from.
out	<i>user_ds</i>	DS segment selector.
out	<i>user_cs</i>	64-bit CS segment selector.
out	<i>user32_cs</i>	32-bit CS segment selector.
	<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. See <a href="#">l4_utcb</a> .


**Returns**

System call error

Definition at line 175 of file [segment.h](#).

References [l4\\_ipc\\_call\(\)](#), [L4\\_IPC\\_NEVER](#), [l4\\_msgtag\(\)](#), [L4\\_PROTO\\_THREAD](#), [L4\\_THREAD\\_AMD64\\_GET\\_SEGMENT\\_INFO\\_OP](#), and [l4\\_msg\\_regs\\_t::mr](#).

Here is the call graph for this function:

**16.70.3.2 fiasco\_amd64\_set\_fs()**

```

long fiasco_amd64_set_fs (
    l4_cap_idx_t thread,
    l4_umword_t base,
    l4_utcb_t * utcb) [inline]

```

Set the base address for the FS segment.

**Parameters**

<i>thread</i>	Thread for which the FS base address shall be modified.
<i>base</i>	Base address.
<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. See <a href="#">l4_utcb</a> .

**Return values**



<i>L4_EOK</i>	Success.
<i>-L4_EINVAL</i>	Invalid base address ( <i>base</i> ).
<i>-L4_ENOSYS</i>	Operation not supported with current kernel configuration.


**Note**

Calling this function is equivalent to calling `fiasco_amd64_set_segment_base(thread, L4_↔AMD64_SEGMENT_FS, base, utcb)`.

Definition at line 203 of file [segment.h](#).

References [L4\\_AMD64\\_SEGMENT\\_FS](#), [l4\\_ipc\\_call\(\)](#), [L4\\_IPC\\_NEVER](#), [l4\\_msgtag\(\)](#), [L4\\_PROTO\\_THREAD](#), and [L4\\_THREAD\\_AMD64\\_SET\\_SEGMENT\\_BASE\\_OP](#).

Here is the call graph for this function:

**16.70.3.3 fiasco\_amd64\_set\_segment\_base()**

```

long fiasco_amd64_set_segment_base (
    l4_cap_idx_t thread,
    enum L4_sys_segment segr,
    l4_umword_t base,
    l4_utcb_t * utcb) [inline]

```

Set the base address for a segment.

**Parameters**

<i>thread</i>	Thread for which the base address of the selected segment shall be modified.
<i>segr</i>	Segment to modify (one of <a href="#">L4_sys_segment</a> ).
<i>base</i>	Base address.
<i>utcb</i>	UTCB to be used for this operation, shall be the UTCB of the calling thread. See <a href="#">l4_utcb</a> .


**Return values**

<code>L4_EOK</code>	Success.
<code>-L4_EINVAL</code>	Invalid segment ( <code>segr</code> ) or base address ( <code>base</code> ).
<code>-L4_ENOSYS</code>	Operation not supported with current kernel configuration.

Definition at line 211 of file [segment.h](#).

References [l4\\_ipc\\_call\(\)](#), [L4\\_IPC\\_NEVER](#), [l4\\_msgtag\(\)](#), [L4\\_PROTO\\_THREAD](#), and [L4\\_THREAD\\_AMD64\\_SET\\_SEGMENT\\_BASE](#).

Here is the call graph for this function:



## 16.71 segment.h

[Go to the documentation of this file.](#)

```

00001
00006 /*
00007  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>
00008  *     economic rights: Technische Universität Dresden (Germany)
00009  *
00010  * License: see LICENSE.spdx (in this directory or the directories above)
00011  */
00012 /*****
00013 #ifndef __L4_SYS__ARCH_X86__SEGMENT_H__
00014 #define __L4_SYS__ARCH_X86__SEGMENT_H__
00015
00016 #ifndef L4API_l4f
00017 #error This header file can only be used with a L4API version!
00018 #endif
00019
00020 #include <l4/sys/ipc.h>
00021
00039 L4_INLINE long
00040 fiasco_ldt_set(l4_cap_idx_t task, void *ldt, unsigned int num_desc,
00041               unsigned int entry_number_start, l4_utcb_t *utcb);
00042
00059 L4_INLINE long
00060 fiasco_gdt_set(l4_cap_idx_t thread, void *desc, unsigned int size,
00061               unsigned int entry_number_start, l4_utcb_t *utcb);
00062
00069 L4_INLINE unsigned
00070 fiasco_gdt_get_entry_offset(l4_cap_idx_t thread, l4_utcb_t *utcb);
00071
00075 enum L4_task_ldt_x86_consts
00076 {
00078     L4_TASK_LDT_X86_ENTRY_SIZE = 8,
00080     L4_TASK_LDT_X86_MAX_ENTRIES
00081         = (L4_UTCB_GENERIC_DATA_SIZE - 2)
00082           / (L4_TASK_LDT_X86_ENTRY_SIZE / (L4_MWORD_BITS / 8)),
00083 };
00084
00100 L4_INLINE long
00101 fiasco_amd64_set_fs(l4_cap_idx_t thread, l4_umword_t base, l4_utcb_t *utcb);
00102
00106 enum L4_sys_segment
00107 {
00109     L4_AMD64_SEGMENT_FS = 0,
00111     L4_AMD64_SEGMENT_GS = 1

```

```

00112 };
00113
00127 L4_INLINE long
00128 fiasco_amd64_set_segment_base(l4_cap_idx_t thread, enum L4_sys_segment segr,
00129                               l4_umword_t base, l4_utcb_t *utcb);
00130
00140 L4_INLINE long
00141 fiasco_amd64_segment_info(l4_cap_idx_t thread, unsigned *user_ds,
00142                           unsigned *user_cs, unsigned *user32_cs,
00143                           l4_utcb_t *utcb);
00144
00145 /*****
00146 *** Implementation
00147 *****/
00148
00149 #include <l4/sys/task.h>
00150 #include <l4/sys/thread.h>
00151
00152 L4_INLINE long
00153 fiasco_ldt_set(l4_cap_idx_t task, void *ldt, unsigned int num_desc,
00154               unsigned int entry_number_start, l4_utcb_t *utcb)
00155 {
00156     if (num_desc > L4_TASK_LDT_X86_MAX_ENTRIES)
00157         return -L4_EINVAL;
00158     l4_utcb_mr_u(utcb)->mr[0] = L4_TASK_LDT_SET_X86_OP;
00159     l4_utcb_mr_u(utcb)->mr[1] = entry_number_start;
00160     __builtin_memcpy(&l4_utcb_mr_u(utcb)->mr[2], ldt,
00161                     num_desc * L4_TASK_LDT_X86_ENTRY_SIZE);
00162     return l4_error_u(l4_ipc_call(task, utcb, l4_msgtag(L4_PROTO_TASK, 2 + num_desc * 2, 0, 0),
00163                          L4_IPC_NEVER), utcb);
00164 }
00165
00165 L4_INLINE unsigned
00166 fiasco_gdt_get_entry_offset(l4_cap_idx_t thread, l4_utcb_t *utcb)
00167 {
00168     l4_utcb_mr_u(utcb)->mr[0] = L4_THREAD_X86_GDT_OP;
00169     if (l4_error_u(l4_ipc_call(thread, utcb, l4_msgtag(L4_PROTO_THREAD, 1, 0, 0), L4_IPC_NEVER), utcb))
00170         return -1;
00171     return l4_utcb_mr_u(utcb)->mr[0];
00172 }
00173
00174 L4_INLINE long
00175 fiasco_amd64_segment_info(l4_cap_idx_t thread, unsigned *user_ds,
00176                           unsigned *user_cs, unsigned *user32_cs,
00177                           l4_utcb_t *utcb)
00178 {
00179     l4_msg_regs_t *m = l4_utcb_mr_u(utcb);
00180     int r;
00181
00182     m->mr[0] = L4_THREAD_AMD64_GET_SEGMENT_INFO_OP;
00183
00184     r = l4_error_u(l4_ipc_call(thread, utcb, l4_msgtag(L4_PROTO_THREAD, 1, 0, 0),
00185                          L4_IPC_NEVER), utcb);
00186     if (r < 0)
00187         return r;
00188
00189     *user_ds = m->mr[0];
00190     *user_cs = m->mr[1];
00191     *user32_cs = m->mr[2];
00192
00193     return 0;
00194 }
00195
00196 #include <l4/sys/compiler.h>
00197
00198 /*****
00199 *** Implementation
00200 *****/
00201
00202 L4_INLINE long
00203 fiasco_amd64_set_fs(l4_cap_idx_t thread, l4_umword_t base, l4_utcb_t *utcb)
00204 {
00205     l4_utcb_mr_u(utcb)->mr[0] = L4_THREAD_AMD64_SET_SEGMENT_BASE_OP | ((l4_umword_t)L4_AMD64_SEGMENT_FS
00206     « 16);
00207     l4_utcb_mr_u(utcb)->mr[1] = base;
00208     return l4_error_u(l4_ipc_call(thread, utcb, l4_msgtag(L4_PROTO_THREAD, 2, 0, 0), L4_IPC_NEVER),
00209                      utcb);
00210 }
00210
00210 L4_INLINE long
00211 fiasco_amd64_set_segment_base(l4_cap_idx_t thread, enum L4_sys_segment segr,
00212                               l4_umword_t base, l4_utcb_t *utcb)
00213 {
00214     l4_utcb_mr_u(utcb)->mr[0] = L4_THREAD_AMD64_SET_SEGMENT_BASE_OP | ((l4_umword_t)segr « 16);
00215     l4_utcb_mr_u(utcb)->mr[1] = base;
00216     return l4_error_u(l4_ipc_call(thread, utcb, l4_msgtag(L4_PROTO_THREAD, 2, 0, 0), L4_IPC_NEVER),
00217                      utcb);

```

```

00217 }
00218
00219 L4_INLINE long
00220 fiasco_gdt_set(l4_cap_idx_t thread, void *desc, unsigned int size,
00221               unsigned int entry_number_start, l4_utcb_t *utcb)
00222 {
00223     l4_utcb_mr_u(utcb)->mr[0] = L4_THREAD_X86_GDT_OP;
00224     l4_utcb_mr_u(utcb)->mr[1] = entry_number_start;
00225     __builtin_memcpy(&l4_utcb_mr_u(utcb)->mr[2], desc, size);
00226     return l4_error_u(l4_ipc_call(thread, utcb, l4_msgtag(L4_PROTO_THREAD, 2 + (size / 8), 0, 0),
00227                       L4_IPC_NEVER), utcb);
00227 }
00228
00229
00230 #endif /* ! __L4_SYS__ARCH_X86__SEGMENT_H__ */

```

## 16.72 x86/l4/sys/segment.h File Reference


Segment handling (x86).

```

#include <l4/sys/ipc.h>
#include <l4/sys/compiler.h>
#include <l4/sys/task.h>
#include <l4/sys/thread.h>

```

Include dependency graph for segment.h:



### Enumerations

- enum `L4_task_ldt_x86_consts` { `L4_TASK_LDT_X86_ENTRY_SIZE` = 8, `L4_TASK_LDT_X86_MAX_ENTRIES` }

Contents for LDT handling.

## Functions

- long [fiasco\\_ldt\\_set](#) ([l4\\_cap\\_idx\\_t](#) task, void \*ldt, unsigned int num\_desc, unsigned int entry\_number\_start, [l4\\_utcb\\_t](#) \*utcb)  
*Set LDT segments descriptors.*
- long [fiasco\\_gdt\\_set](#) ([l4\\_cap\\_idx\\_t](#) thread, void \*desc, unsigned int size, unsigned int entry\_number\_start, [l4\\_utcb\\_t](#) \*utcb)  
*Set GDT segment descriptors.*
- unsigned [fiasco\\_gdt\\_get\\_entry\\_offset](#) ([l4\\_cap\\_idx\\_t](#) thread, [l4\\_utcb\\_t](#) \*utcb)  
*Return the offset of the entry in the GDT.*

## 16.72.1 Detailed Description

Segment handling (x86).

Definition in file [segment.h](#).

## 16.72.2 Enumeration Type Documentation

### 16.72.2.1 L4\_task\_ldt\_x86\_consts

enum [L4\\_task\\_ldt\\_x86\\_consts](#)

Constants for LDT handling.

#### Enumerator

L4_TASK_LDT_X86_ENTRY_SIZE	Size of an LDT entry.
L4_TASK_LDT_X86_MAX_ENTRIES	Maximum number of LDT entries that can be written with one call.

Definition at line 75 of file [segment.h](#).

## 16.73 segment.h

[Go to the documentation of this file.](#)

```

00001
00006 /*
00007  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>
00008  *      economic rights: Technische Universität Dresden (Germany)
00009  *
00010  * License: see LICENSE.spdx (in this directory or the directories above)
00011  */
00012 /*****
00013 #ifndef __L4_SYS__ARCH_X86__SEGMENT_H__
00014 #define __L4_SYS__ARCH_X86__SEGMENT_H__
00015
00016 #ifndef L4API_L4f
00017 #error This header file can only be used with a L4API version!
00018 #endif
00019
00020 #include <l4/sys/ipc.h>
00021
00039 L4_INLINE long
00040 fiasco_ldt_set(l4_cap_idx_t task, void *ldt, unsigned int num_desc,
00041               unsigned int entry_number_start, l4_utcb_t *utcb);

```

```

00042
00059 L4_INLINE long
00060 fiasco_gdt_set(l4_cap_idx_t thread, void *desc, unsigned int size,
00061               unsigned int entry_number_start, l4_utcb_t *utcb);
00062
00069 L4_INLINE unsigned
00070 fiasco_gdt_get_entry_offset(l4_cap_idx_t thread, l4_utcb_t *utcb);
00071
00075 enum L4_task_ldt_x86_consts
00076 {
00078     L4_TASK_LDT_X86_ENTRY_SIZE = 8,
00080     L4_TASK_LDT_X86_MAX_ENTRIES
00081     = (L4_UTCB_GENERIC_DATA_SIZE - 2)
00082       / (L4_TASK_LDT_X86_ENTRY_SIZE / (L4_MWORD_BITS / 8)),
00083 };
00084
00085 /*****
00086  *** Implementation
00087  *****/
00088
00089 #include <l4/sys/compiler.h>
00090 #include <l4/sys/task.h>
00091 #include <l4/sys/thread.h>
00092
00093 L4_INLINE long
00094 fiasco_ldt_set(l4_cap_idx_t task, void *ldt, unsigned int num_desc,
00095               unsigned int entry_number_start, l4_utcb_t *utcb)
00096 {
00097     if (num_desc > L4_TASK_LDT_X86_MAX_ENTRIES)
00098         return -L4_EINVAL;
00099     l4_utcb_mr_u(utcb)->mr[0] = L4_TASK_LDT_SET_X86_OP;
00100     l4_utcb_mr_u(utcb)->mr[1] = entry_number_start;
00101     __builtin_memcpy(&l4_utcb_mr_u(utcb)->mr[2], ldt,
00102                     num_desc * L4_TASK_LDT_X86_ENTRY_SIZE);
00103     return l4_error_u(l4_ipc_call(task, utcb, l4_msgtag(L4_PROTO_TASK, 2 + num_desc * 2, 0, 0),
00104                        L4_IPC_NEVER), utcb);
00105 }
00106
00107 L4_INLINE unsigned
00108 fiasco_gdt_get_entry_offset(l4_cap_idx_t thread, l4_utcb_t *utcb)
00109 {
00110     l4_utcb_mr_u(utcb)->mr[0] = L4_THREAD_X86_GDT_OP;
00111     if (l4_error_u(l4_ipc_call(thread, utcb, l4_msgtag(L4_PROTO_THREAD, 1, 0, 0), L4_IPC_NEVER), utcb))
00112         return -1;
00113     return l4_utcb_mr_u(utcb)->mr[0];
00114 }
00115
00116 L4_INLINE long
00117 fiasco_gdt_set(l4_cap_idx_t thread, void *desc, unsigned int size,
00118               unsigned int entry_number_start, l4_utcb_t *utcb)
00119 {
00120     l4_utcb_mr_u(utcb)->mr[0] = L4_THREAD_X86_GDT_OP;
00121     l4_utcb_mr_u(utcb)->mr[1] = entry_number_start;
00122     __builtin_memcpy(&l4_utcb_mr_u(utcb)->mr[2], desc, size);
00123     return l4_error_u(l4_ipc_call(thread, utcb, l4_msgtag(L4_PROTO_THREAD, 2 + (size >> 2), 0, 0),
00124                        L4_IPC_NEVER), utcb);
00125 }
00126
00127 #endif /* ! __L4_SYS_ARCH_X86_SEGMENT_H */

```

## 16.74 amd64/l4/util/perform.h File Reference


Performance Monitoring using P5/P6 Measurement Counters.

```

#include <l4/sys/types.h>
#include <l4/sys/compiler.h>

```

Include dependency graph for perform.h:



### 16.74.1 Detailed Description

Performance Monitoring using P5/P6 Measurement Counters.

Define either `CPU_PENTIUM` or `CPU_P6`

Definition in file [perform.h](#).

## 16.75 perform.h

[Go to the documentation of this file.](#)

```

00001
00002 /*
00003  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00004  *      Torsten Frenzel <frenzel@os.inf.tu-dresden.de>
00005  *      economic rights: Technische Universität Dresden (Germany)
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00008 #ifndef __L4UTIL_PERFORM_H
00009 #define __L4UTIL_PERFORM_H
00010
00011 #include <l4/sys/types.h>
00012 #include <l4/sys/compiler.h>
00013
00014 L4_BEGIN_DECLS
00015
00016 extern const char*strp6pmc_event(l4_uint32_t event);
00017
00018 #ifndef CONFIG_PERFORM_ONLY_PROTOTYPES
00019 #if ! (defined CPU_PENTIUM ^ defined CPU_P6 ^ defined CPU_K7)
00020 #error You must define your target architecture.
00021 #error Define EITHER CPU_PENTIUM for Intel Pentium or CPU_P6 for Intel PPro/PII/PIII.
00022 #else
00023 /* P5/P6/K7 section */
00024 #endif
00025 #endif

```

```

00034 /* Makros for access to model specific registers (MSR) */
00035
00036 /* Write the 64-Bit Model Specific Register. First argument is the register,
00037    second the 64-Bit value. This can only be called at privilege level 0.
00038    With L4, the kernel emulates the WRMSR when calling in PL 3.
00039    */
00040 static inline void l4_i586_wrmsr(unsigned reg,unsigned long long*val){
00041     unsigned long dummyeax, dummyecx, dummyedx;
00042
00043     asm volatile(
00044         ".byte 0xf; .byte 0x30\n" /* wrmsr */
00045         : "=a" (dummyeax), "=d" (dummyedx), "=c" (dummyecx)
00046         : "2" (reg), "0" (*(unsigned *)val), "1" (*(unsigned *)val+1))
00047     );
00048 }
00049
00050 /* Read the 64-Bit Model Specific Register. First argument is the register,
00051    second the address to a 64-Bit value. This can only be called at
00052    privilege level 0. With L4, the kernel emulates the RDMSR when calling
00053    in PL 3.
00054    */
00055 static inline void l4_i586_rdmsr(unsigned reg,unsigned long long*val){
00056     unsigned dummy;
00057
00058     asm volatile(
00059         ".byte 0xf; .byte 0x32\n" /* rdmsr */
00060         : "=a" (*(unsigned *)val), "=d" (*(unsigned *)val+1), "=c" (dummy)
00061         : "2" (reg)
00062     );
00063 }
00064
00065 #ifdef CPU_PENTIUM
00066 /* Pentium section */
00067
00068 /* functions and events defined here are only usable at Pentium
00069    Processors. P6 architecture does NOT support this kind of measuring and
00070    these events. P6 architecture has its own counters and its own events.
00071    See P6-section for details. */
00072
00073 /* from l4linux/arch/l4-i386/include/perform.h */
00074
00075 static inline void
00076 l4_i586_reset_event_counter(void){
00077     asm volatile("xor %%rax, %%rax\n"
00078         "xor %%rdx, %%rdx\n"
00079         "mov $0x12, %%rcx\n"
00080         ".byte 0x0f, 0x30\n"
00081         "movl $0x13, %%rcx\n"
00082         ".byte 0x0f, 0x30\n"
00083         : : : "cx", "ax", "dx"
00084     );
00085 }
00086
00087 static inline void
00088 l4_i586_read_event_counter_long(long long *counter0, long long *counter1)
00089 {
00090     asm volatile(
00091         /* "movl $0, %%eax\n"
00092         "movl $0x11, %%ecx\n"
00093         ".byte 0x0f, 0x30\n" */ /* stop event counting */
00094         "mov $0x12, %%rcx\n"
00095         ".byte 0x0f, 0x32\n"
00096         "mov %%rax, (%%%rbx)\n"
00097         "mov %%rdx, 4(%%rbx)\n"
00098         "mov $0x13, %%ecx\n"
00099         ".byte 0x0f, 0x32\n"
00100         "mov %%rax, (%%%rsi)\n"
00101         "mov %%rdx, 4(%%rsi)\n"
00102         : /* no output */
00103         : "b" (counter0), "S" (counter1)
00104         : "ax", "cx", "dx"
00105     );
00106 }
00107
00108 static inline void
00109 l4_i586_read_event_counter(int *counter0, int *counter1)
00110 {
00111     asm volatile("push %%rdx \n"
00112         ".byte 0x0f, 0x30 \n"
00113         "mov $0x12, %%rcx \n"
00114         ".byte 0x0f, 0x32 \n"
00115         "mov %%rax, %%rbx \n"
00116         "movl $0x13, %%rcx \n"
00117         ".byte 0x0f, 0x32\n"
00118         "popl %%edx\n"
00119         : "=b" (*counter0), "=a" (*counter1)

```



```

00121         : "l" (0), "c" (0x11)
00122     );
00123 }
00124
00125 static inline void
00126 l4_i586_select_event(int event0, int event1)
00127 {
00128     asm volatile(".byte 0x0f, 0x30\n"
00129         :
00130         :
00131         "a" (event0 + (event1 < 16)),
00132         "d" (0),
00133         "c" (0x11)
00134     );
00135 };
00136
00137 #define P5_RD_MISS          0x003 /* 000011B */
00138 #define P5_WR_MISS          0x008 /* 000100B */
00139 #define P5_RW_MISS          0x029 /* 101001B */
00140 #define P5_EX_MISS          0x00e /* 001110B */
00141
00142 #define P5_D_WBACK          0x006 /* 000110B */
00143
00144 #define P5_RW_TLB           0x002 /* 00010B */
00145 #define P5_EX_TLB           0x00d /* 01101B */
00146
00147 #define P5_A_STALL          0x01f /* 11111B */
00148 #define P5_W_STALL          0x019 /* 11001B */
00149 #define P5_R_STALL          0x01a /* 11010B */
00150 #define P5_X_STALL          0x01b /* 11011B */
00151
00152 #define P5_AGI_STALL         0x01f /* 11111B */
00153
00154 #define P5_PIPELINE_FLUSH   0x015 /* 10101B */
00155
00156 #define P5_NON_CACHE_RD     0x01e /* 11110B */
00157 #define P5_NCACHE_REFS     0x01e /* 11110B */
00158 #define P5_LOCKED_BUS       0x01c /* 11100B */
00159
00160 #define P5_MEM2PIPE         0x009 /* 01001B */
00161 #define P5_BANK_CONF        0x00a /* 01010B */
00162
00163
00164 #define P5_INSTRS_EX         0x016 /* 10110B */
00165 #define P5_INSTRS_EX_V      0x017 /* 10111B */
00166
00167
00168 #define P5_CNT_NOTHING      (0x00 < 6) /* 00B < 6 */
00169 #define P5_CNT_EVENT_PL0    (0x01 < 6) /* 01B < 6 */
00170 #define P5_CNT_EVENT_PL3    (0x02 < 6) /* 10B < 6 */
00171 #define P5_CNT_EVENT        (0x03 < 6) /* 11B < 6 */
00172 #define P5_CNT_CLOCKS_PL0   (0x05 < 6) /* 101B < 6 */
00173 #define P5_CNT_CLOCKS_PL3   (0x06 < 6) /* 110B < 6 */
00174 #define P5_CNT_CLOCKS       (0x07 < 6) /* 111B < 6 */
00175
00176
00177 #else
00178 #if defined CPU_P6
00179 /* PPro/PII/PIII section */
00180
00181 /*-
00182  * Copyright (c) 1997 The President and Fellows of Harvard College.
00183  * All rights reserved.
00184  * Copyright (c) 1997 Aaron B. Brown.
00185  *
00186  * Redistribution and use in source and binary forms, with or without
00187  * modification, are permitted provided that the following conditions
00188  * are met:
00189  * 1. Redistributions of source code must retain the above copyright
00190  * notice, this list of conditions and the following disclaimer.
00191  * 2. Redistributions in binary form must reproduce the above copyright
00192  * notice, this list of conditions and the following disclaimer in the
00193  * documentation and/or other materials provided with the distribution.
00194  * 3. All advertising materials mentioning features or use of this software
00195  * must display the following acknowledgement:
00196  * This product includes software developed by Harvard University
00197  * and its contributors.
00198  * 4. Neither the name of the University nor the names of its contributors
00199  * may be used to endorse or promote products derived from this software
00200  * without specific prior written permission.
00201  *
00202  * THIS SOFTWARE IS PROVIDED BY HARVARD AND CONTRIBUTORS ``AS IS" AND
00203  * ANY EXPRESS OR IMPLIED WARRANTIES, INCLUDING, BUT NOT LIMITED TO, THE
00204  * IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE
00205  * ARE DISCLAIMED. IN NO EVENT SHALL HARVARD UNIVERSITY OR CONTRIBUTORS BE
00206  * LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, EXEMPLARY, OR
00207  * CONSEQUENTIAL DAMAGES (INCLUDING, BUT NOT LIMITED TO, PROCUREMENT OF

```

```

00208 * SUBSTITUTE GOODS OR SERVICES; LOSS OF USE, DATA, OR PROFITS; OR BUSINESS
00209 * INTERRUPTION) HOWEVER CAUSED AND ON ANY THEORY OF LIABILITY, WHETHER IN
00210 * CONTRACT, STRICT LIABILITY, OR TORT (INCLUDING NEGLIGENCE OR OTHERWISE)
00211 * ARISING IN ANY WAY OUT OF THE USE OF THIS SOFTWARE, EVEN IF ADVISED OF THE
00212 * POSSIBILITY OF SUCH DAMAGE.
00213 */
00214
00215 /*****
00216 ** Symbolic names for counter numbers (used in select_p6counter()) **
00217 *****/
00218 *
00219 * These correspond in order to the Pentium Pro counters. Add new counters at
00220 * the end. These agree with the mnemonics in the Pentium Pro Family
00221 * Developer's Manual, vol 3.
00222 *
00223 * Those events marked with a $ require a MESI unit field; those marked with
00224 * a @ require a self/any unit field. Those marked with a 0 are only supported
00225 * in counter 0; those marked with 1 are only supported in counter 1.
00226 */
00227
00228 /* Data cache unit */
00229 #define P6_DATA_MEM_REFS 0x43 /* total memory refs */
00230 #define P6_DCU_LINES_IN 0x45 /* all lines allocated in cache unit */
00231 #define P6_DCU_M_LINES_IN 0x46 /* M lines allocated in cache unit */
00232 #define P6_DCU_M_LINES_OUT 0x47 /* M lines evicted from cache */
00233 #define P6_DCU_MISS_OUTSTANDING 0x48 /* #cycles a miss is outstanding */
00234
00235 /* Instruction fetch unit */
00236 #define P6_IFU_IFETCH 0x80 /* instruction fetches */
00237 #define P6_IFU_IFETCH_MISS 0x81 /* instruction fetch misses */
00238 #define P6_ITLB_MISS 0x85 /* ITLB misses */
00239 #define P6_IFU_MEM_STALL 0x86 /* number of cycles IFU is stalled */
00240 #define P6_ILD_STALL 0x87 /* #stalls in instr length decode */
00241
00242 /* L2 Cache */
00243 #define P6_L2_IFETCH 0x28 /* ($) 12 ifetches */
00244 #define P6_L2_LD 0x29 /* ($) 12 data loads */
00245 #define P6_L2_ST 0x2a /* ($) 12 data stores */
00246 #define P6_L2_LINES_IN 0x24 /* lines allocated in L2 */
00247 #define P6_L2_LINES_OUT 0x26 /* lines removed from L2 */
00248 #define P6_L2_M_LINES_INM 0x25 /* modified lines allocated in L2 */
00249 #define P6_L2_M_LINES_OUTM 0x27 /* modified lines removed from L2 */
00250 #define P6_L2_RQSTS 0x2e /* ($) number of l2 requests */
00251 #define P6_L2_ADS 0x21 /* number of l2 addr strobes */
00252 #define P6_L2_DBUS_BUSY 0x22 /* number of data bus busy cycles */
00253 #define P6_L2_DBUS_BUSY_RD 0x23 /* #bus cycles xferring l2->cpu */
00254
00255 /* External bus logic */
00256 #define P6_BUS_DRDY_CLOCKS 0x62 /* (@) #clocks DRDY is asserted */
00257 #define P6_BUS_LOCK_CLOCKS 0x63 /* (@) #clocks LOCK is asserted */
00258 #define P6_BUS_REQ_OUTSTANDING 0x60 /* #bus requests outstanding */
00259 #define P6_BUS_TRAN_BRD 0x65 /* (@) bus burst read txns */
00260 #define P6_BUS_TRAN_RFO 0x66 /* (@) bus read for ownership txns */
00261 #define P6_BUS_TRAN_WB 0x67 /* (@) bus writeback txns */
00262 #define P6_BUS_TRAN_IFETCH 0x68 /* (@) bus instr fetch txns */
00263 #define P6_BUS_TRAN_INVALID 0x69 /* (@) bus invalidate txns */
00264 #define P6_BUS_TRAN_PWR 0x6a /* (@) bus partial write txns */
00265 #define P6_BUS_TRANS_P 0x6b /* (@) bus partial txns */
00266 #define P6_BUS_TRANS_IO 0x6c /* (@) bus I/O txns */
00267 #define P6_BUS_TRAN_DEF 0x6d /* (@) bus deferred txns */
00268 #define P6_BUS_TRAN_BURST 0x6e /* (@) bus burst txns */
00269 #define P6_BUS_TRAN_ANY 0x70 /* (@) total bus txns */
00270 #define P6_BUS_TRAN_MEM 0x6f /* (@) total memory txns */
00271 #define P6_BUS_DATA_RCV 0x64 /* #busclocks CPU is receiving data */
00272 #define P6_BUS_BNR_DRV 0x61 /* #busclocks CPU is driving BNR pin */
00273 #define P6_BUS_HIT_DRV 0x7a /* #busclocks CPU is driving HIT pin */
00274 #define P6_BUS_HITM_DRV 0x7b /* #busclocks CPU is driving HITM pin */
00275 #define P6_BUS_SNOOP_STALL 0x7e /* #clkcycles bus is snoop-stalled */
00276
00277 /* FPU */
00278 #define P6_FLOPS 0xc1 /* (0) number of FP ops retired */
00279 #define P6_FP_COMP_OPS 0x10 /* (0) computational FPOPS exec'd */
00280 #define P6_FP_ASSIST 0x11 /* (1) FP excep's handled in ucode */
00281 #define P6_MUL 0x12 /* (1) number of FP multiplies */
00282 #define P6_DIV 0x13 /* (1) number of FP divides */
00283 #define P6_CYCLES_DIV_BUSY 0x14 /* (0) number of cycles divider busy */
00284
00285 /* Memory ordering */
00286 #define P6_LD_BLOCKS 0x03 /* number of store buffer blocks */
00287 #define P6_SB_DRAINS 0x04 /* # of store buffer drain cycles */
00288 #define P6_MISALING_MEM_REF 0x05 /* # misaligned data memory refs */
00289
00290 /* Instruction decoding and retirement */
00291 #define P6_INST_RETIRED 0xc0 /* number of instrs retired */
00292 #define P6_OPS_RETIRED 0xc2 /* number of micro-ops retired */
00293 #define P6_INST_DECODER 0xd0 /* number of instructions decoded */
00294

```

```

00295 /* Interrupts */
00296 #define P6_HW_INT_RX 0xc8 /* number of hardware interrupts */
00297 #define P6_CYCLES_INT_MASKED 0xc6 /* number of cycles hardints masked */
00298 #define P6_CYCLES_INT_PENDING_AND_MASKED 0xc7 /* #cycles masked but pending */
00299
00300 /* Branches */
00301 #define P6_BR_INST_RETIRED 0xc4 /* number of branch instrs retired */
00302 #define P6_BR_MISS_PRED_RETIRED 0xc5 /* number of mispred'd brs retired */
00303 #define P6_BR_TAKEN_RETIRED 0xc9 /* number of taken branches retired */
00304 #define P6_BR_MISS_PRED_TAKEN_RET 0xca /* #taken mispredictions br's retired */
00305 #define P6_BR_INST_DECODED 0xe0 /* number of branch instrs decoded */
00306 #define P6_BTBMISSES 0xe2 /* # of branches that missed in BTB */
00307 #define P6_BR_BOGUS 0xe4 /* number of bogus branches */
00308 #define P6_BACLEAR 0xe6 /* # times BACLEAR is asserted */
00309
00310 /* Stalls */
00311 #define P6_RESOURCE_STALLS 0xa2 /* # resource-related stall cycles */
00312 #define P6_PARTIAL_RAT_STALLS 0xd2 /* # cycles/events for partial stalls */
00313
00314 /* Segment register loads */
00315 #define P6_SEGMENT_REG_LOADS 0x06 /* number of segment register loads */
00316
00317 /* Clocks */
00318 #define P6_CPU_CLK_UNHALTED 0x79 /* #clocks CPU is not halted */
00319
00320 /* Unit field tags */
00321 #define P6_UNIT_M 0x0800
00322 #define P6_UNIT_E 0x0400
00323 #define P6_UNIT_S 0x0200
00324 #define P6_UNIT_I 0x0100
00325 #define P6_UNIT_MESI 0x0f00
00326
00327 #define P6_UNIT_SELF 0x0000
00328 #define P6_UNIT_ANY 0x2000
00329
00330 /*****
00331  ** Flag bit definitions (used for the 'flag' field in select_p6counter()) **
00332  *****/
00333 *
00334 * The driver accepts fully-formed counter specifications from user-level.
00335 * The following flags are mnemonics for the bits that get set in the
00336 * PerfEvtSel0 and PerfEvtSel1 MSR's
00337 *
00338 */
00339 #define P6CNT_U 0x010000 /* Monitor user-level events */
00340 #define P6CNT_K 0x020000 /* Monitor kernel-level events */
00341 #define P6CNT_E 0x040000 /* Edge detect: count state transitions */
00342 #define P6CNT_PC 0x080000 /* Pin control: ?? */
00343 #define P6CNT_IE 0x100000 /* Int enable: enable interrupt on overflow */
00344 #define P6CNT_F 0x200000 /* Freeze counter (handled in software) */
00345 #define P6CNT_EN 0x400000 /* enable counters (in PerfEvtSel0) */
00346 #define P6CNT_IV 0x800000 /* Invert counter mask comparison result */
00347
00348 /*****
00349  ** Miscellaneous constants **
00350  *****/
00351 *
00352 * Number of Pentium Pro programable hardware counters.
00353 */
00354 #define NUM_P6HWC 2
00355
00356 /*****
00357  *
00358  * End of Copyright by Harvard College
00359  *
00360  *****/
00361
00362
00363 #define MSR_P6_EVTSEL0 0x186
00364 #define MSR_P6_EVTSEL1 0x187
00365 #define MSR_P6_PERFCTR0 0xc1
00366 #define MSR_P6_PERFCTR1 0xc2
00367
00368 /* P6-specific Makros to manipulate and read counters */
00369
00370 /* Read the 40 bit performance monitoring counter. This requires
00371 the PCE-flag in CR4 to be set. Otherwise GP0 is raised. Works only
00372 at P6.
00373 */
00374 #define l4_i686_rdpmc(cnt, res_p) \
00375 __asm __volatile( \
00376 "mov %2, %%rcx # put counter number in \n\
00377 .byte 0xf, .byte 0x33 # RDPMC instruction \n\
00378 mov %%rdx, %1 # High order 32 bits \n\
00379 mov %%rax, %0 # Low order 32 bits" \
00380 : "=g" (*(int *) (res_p)), "=g" (((int *) res_p)+1)) \
00381 : "g" (cnt) \

```

```

00382 : "ecx", "eax", "edx")
00383
00384 static inline l4_uint32_t l4_i686_rdpmc_32(int cnt){
00385     l4_uint32_t x;
00386
00387     __asm__ __volatile__(
00388         ".byte 0xf; .byte 0x33 # RDPMC instruction"
00389         : "=a" (x)
00390         : "c" (cnt)
00391         : "rcx", "rax", "rdx");
00392     return x;
00393 }
00394
00395 static inline void l4_i686_select_perfctr_event(int counter,
00396                                                 unsigned long long val){
00397     l4_i586_wrmsr(MSR_P6_EVNTSEL0+counter, &val);
00398 }
00399
00400 static inline void l4_i686_select_perfctr0_event(long long *val){
00401     __asm volatile(
00402         "mov $MSR_P6_EVNTSEL0, %%rcx\n"
00403         "mov (%%rbx), %%rax\n"
00404         "mov 4(%%rbx), %%rdx\n"
00405         /* ".byte 0xcc, 0xeb, 0x01, 0x21\n"
00406         ".byte 0x0f, 0x30\n" // wrmsr
00407         /* ".byte 0xcc, 0xeb, 0x01, 0x21\n"
00408         : /* no output */
00409         : "b" (val)
00410         : "ax", "cx", "dx", "bx"
00411         );
00412
00413 }
00414
00415 /* end of P6 section */
00416 #else
00417
00418 #define K7CNT_U 0x010000 /* Monitor user-level events */
00419 #define K7CNT_K 0x020000 /* Monitor kernel-level events */
00420 #define K7CNT_E 0x040000 /* Edge detect: count state transitions */
00421 #define K7CNT_PC 0x080000 /* Pin control: ?? */
00422 #define K7CNT_IE 0x100000 /* Int enable: enable interrupt on overflow */
00423 #define K7CNT_F 0x200000 /* Freeze counter (handled in software) */
00424 #define K7CNT_EN 0x400000 /* enable counters (in PerfEvtSel0) */
00425 #define K7CNT_IV 0x800000 /* Invert counter mask comparison result */
00426
00427 #define MSR_K7_EVNTSEL0 0xC0010000
00428 #define MSR_K7_EVNTSEL1 0xC0010001
00429 #define MSR_K7_EVNTSEL2 0xC0010002
00430 #define MSR_K7_EVNTSEL3 0xC0010003
00431 #define MSR_K7_PERFCTR0 0xC0010004
00432 #define MSR_K7_PERFCTR1 0xC0010005
00433 #define MSR_K7_PERFCTR2 0xC0010006
00434 #define MSR_K7_PERFCTR3 0xC0010007
00435
00436 #endif
00437
00438 #endif
00439
00440 /* end of P5/P6/K7 section*/
00441 #endif
00442
00443 /* end of not only lib-prototypes section */
00444 #endif
00445
00446 L4_END_DECLS
00447
00448 #endif

```

## 16.76 x86/i4/util/perform.h File Reference


Performance Monitoring using P5/P6 Measurement Counters.

```

#include <l4/sys/types.h>
#include <l4/sys/compiler.h>

```

Include dependency graph for perform.h:



### 16.76.1 Detailed Description

Performance Monitoring using P5/P6 Measurement Counters.

Define either `CPU_PENTIUM` or `CPU_P6`

Definition in file [perform.h](#).

## 16.77 perform.h

[Go to the documentation of this file.](#)

```

00001
00007 /*
00008  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00009  *               Frank Mehnert <fm3@os.inf.tu-dresden.de>,
00010  *               Lars Reuther <reuther@os.inf.tu-dresden.de>
00011  *               economic rights: Technische Universität Dresden (Germany)
00012  * License: see LICENSE.spdx (in this directory or the directories above)
00013  */
00014
00015 #ifndef __L4UTIL_PERFORM_H
00016 #define __L4UTIL_PERFORM_H
00017
00018 #include <l4/sys/types.h>
00019 #include <l4/sys/compiler.h>
00020
00021 L4_BEGIN_DECLS
00022
00023 extern const char*strp6pmc_event(l4_uint32_t event);
00024
00025 #ifndef CONFIG_PERFORM_ONLY_PROTOTYPES
00026
00027 #if ! (defined CPU_PENTIUM ^ defined CPU_P6 ^ defined CPU_K7)
00028
00029 #error You must define your target architecture.
00030 #error Define EITHER CPU_PENTIUM for Intel Pentium or CPU_P6 for Intel PPro/PII/PIII.
00031
00032 #else
00033

```

```

00034 /* P5/P6/K7 section */
00035
00036 /* Makros for access to model specific registers (MSR) */
00037
00038 /* Write the 64-Bit Model Specific Register. First argument is the register,
00039    second the 64-Bit value. This can only be called at privilege level 0.
00040    With L4, the kernel emulates the WRMSR when calling in PL 3.
00041    */
00042 static inline void l4_i586_wrmsr(unsigned reg,unsigned long long*val){
00043     unsigned long dummyeax, dummyecx, dummyedx;
00044
00045     asm volatile(
00046         ".byte 0xf; .byte 0x30\n" /* wrmsr */
00047         : "=a" (dummyeax), "=d" (dummyedx), "=c" (dummyecx)
00048         : "2" (reg), "0" (*(unsigned *)val), "1" (*(unsigned *)val+1))
00049     );
00050 }
00051
00052 /* Read the 64-Bit Model Specific Register. First argument is the register,
00053    second the address to a 64-Bit value. This can only be called at
00054    privilege level 0. With L4, the kernel emulates the RDMSR when calling
00055    in PL 3.
00056    */
00057 static inline void l4_i586_rdmsr(unsigned reg,unsigned long long*val){
00058     unsigned dummy;
00059
00060     asm volatile(
00061         ".byte 0xf; .byte 0x32\n" /* rdmsr */
00062         : "=a" (*(unsigned *)val), "=d" (*(unsigned *)val+1), "=c" (dummy)
00063         : "2" (reg)
00064     );
00065 }
00066
00067
00068 #ifdef CPU_PENTIUM
00069 /* Pentium section */
00070
00071 /* functions and events defined here are only usable at Pentium
00072    Processors. P6 architecture does NOT support this kind of measuring and
00073    these events. P6 architecture has its own counters and its own events.
00074    See P6-section for details. */
00075
00076 /* from l4linux/arch/l4-i386/include/perform.h */
00077
00078 static inline void
00079 l4_i586_reset_event_counter(void){
00080     asm volatile("xor %%eax, %%eax\n"
00081         "xor %%edx, %%edx\n"
00082         "movl $0x12, %%ecx\n"
00083         ".byte 0x0f, 0x30\n"
00084         "movl $0x13, %%ecx\n"
00085         ".byte 0x0f, 0x30\n"
00086         : : : "cx", "ax", "dx"
00087     );
00088 };
00089
00090 static inline void
00091 l4_i586_read_event_counter_long(long long *counter0, long long *counter1)
00092 {
00093     asm volatile(
00094         /*      "movl $0, %%eax\n"
00095         "movl $0x11, %%ecx\n"
00096         ".byte 0x0f, 0x30\n" *//* stop event counting */
00097         "movl $0x12, %%ecx\n"
00098         ".byte 0x0f, 0x32\n"
00099         "movl %%eax, (%%ebx)\n"
00100         "movl %%edx, 4(%%ebx)\n"
00101         "movl $0x13, %%ecx\n"
00102         ".byte 0x0f, 0x32\n"
00103         "movl %%eax, (%%esi)\n"
00104         "movl %%edx, 4(%%esi)\n"
00105         : /* no output */
00106         : "b" (counter0), "S" (counter1)
00107         : "ax", "cx", "dx"
00108     );
00109 }
00110
00111 static inline void
00112 l4_i586_read_event_counter(int *counter0, int *counter1)
00113 {
00114     asm volatile("pushl %%edx\n"
00115         ".byte 0x0f, 0x30\n"
00116         "movl $0x12, %%ecx\n"
00117         ".byte 0x0f, 0x32\n"
00118         "movl %%eax, %%ebx\n"
00119         "movl $0x13, %%ecx\n"
00120         ".byte 0x0f, 0x32\n"

```

```

00121         "popl  %%edx\n"
00122         : "=b" (*counter0), "a" (*counter1)
00123         : "1" (0), "c" (0x11)
00124         );
00125     }
00126
00127     static inline void
00128     l4_i586_select_event(int event0, int event1)
00129     {
00130         asm volatile(".byte 0x0f, 0x30\n"
00131             :
00132             :
00133             "a" (event0 + (event1 < 16)),
00134             "d" (0),
00135             "c" (0x11)
00136             );
00137     };
00138
00139     #define P5_RD_MISS          0x003 /* 000011B */
00140     #define P5_WR_MISS          0x008 /* 000100B */
00141     #define P5_RW_MISS          0x029 /* 101001B */
00142     #define P5_EX_MISS          0x00e /* 001110B */
00143
00144     #define P5_D_WBACK          0x006 /* 000110B */
00145
00146     #define P5_RW_TLB           0x002 /* 00010B */
00147     #define P5_EX_TLB           0x00d /* 01101B */
00148
00149     #define P5_A_STALL           0x01f /* 11111B */
00150     #define P5_W_STALL           0x019 /* 11001B */
00151     #define P5_R_STALL           0x01a /* 11010B */
00152     #define P5_X_STALL           0x01b /* 11011B */
00153
00154     #define P5_AGI_STALL         0x01f /* 11111B */
00155
00156     #define P5_PIPELINE_FLUSH    0x015 /* 10101B */
00157
00158     #define P5_NON_CACHE_RD      0x01e /* 11110B */
00159     #define P5_NCACHE_REFS       0x01e /* 11110B */
00160     #define P5_LOCKED_BUS        0x01c /* 11100B */
00161
00162     #define P5_MEM2PIPE           0x009 /* 01001B */
00163     #define P5_BANK_CONF         0x00a /* 01010B */
00164
00165
00166     #define P5_INSTRS_EX          0x016 /* 10110B */
00167     #define P5_INSTRS_EX_V        0x017 /* 10111B */
00168
00169
00170     #define P5_CNT_NOTHING        (0x00 < 6) /* 00B < 6 */
00171     #define P5_CNT_EVENT_PL0      (0x01 < 6) /* 01B < 6 */
00172     #define P5_CNT_EVENT_PL3      (0x02 < 6) /* 10B < 6 */
00173     #define P5_CNT_EVENT          (0x03 < 6) /* 11B < 6 */
00174     #define P5_CNT_CLOCKS_PL0     (0x05 < 6) /* 101B < 6 */
00175     #define P5_CNT_CLOCKS_PL3     (0x06 < 6) /* 110B < 6 */
00176     #define P5_CNT_CLOCKS         (0x07 < 6) /* 111B < 6 */
00177
00178
00179     #else
00180     #if defined CPU_P6
00181     /* PPro/PII/PIII section */
00182
00183     /*-
00184     * Copyright (c) 1997 The President and Fellows of Harvard College.
00185     * All rights reserved.
00186     * Copyright (c) 1997 Aaron B. Brown.
00187     *
00188     * Redistribution and use in source and binary forms, with or without
00189     * modification, are permitted provided that the following conditions
00190     * are met:
00191     * 1. Redistributions of source code must retain the above copyright
00192     *   notice, this list of conditions and the following disclaimer.
00193     * 2. Redistributions in binary form must reproduce the above copyright
00194     *   notice, this list of conditions and the following disclaimer in the
00195     *   documentation and/or other materials provided with the distribution.
00196     * 3. All advertising materials mentioning features or use of this software
00197     *   must display the following acknowledgement:
00198     *       This product includes software developed by Harvard University
00199     *       and its contributors.
00200     * 4. Neither the name of the University nor the names of its contributors
00201     *   may be used to endorse or promote products derived from this software
00202     *   without specific prior written permission.
00203     *
00204     * THIS SOFTWARE IS PROVIDED BY HARVARD AND CONTRIBUTORS ``AS IS'' AND
00205     * ANY EXPRESS OR IMPLIED WARRANTIES, INCLUDING, BUT NOT LIMITED TO, THE
00206     * IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE
00207     * ARE DISCLAIMED.  IN NO EVENT SHALL HARVARD UNIVERSITY OR CONTRIBUTORS BE

```

```

00208 * LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, EXEMPLARY, OR
00209 * CONSEQUENTIAL DAMAGES (INCLUDING, BUT NOT LIMITED TO, PROCUREMENT OF
00210 * SUBSTITUTE GOODS OR SERVICES; LOSS OF USE, DATA, OR PROFITS; OR BUSINESS
00211 * INTERRUPTION) HOWEVER CAUSED AND ON ANY THEORY OF LIABILITY, WHETHER IN
00212 * CONTRACT, STRICT LIABILITY, OR TORT (INCLUDING NEGLIGENCE OR OTHERWISE)
00213 * ARISING IN ANY WAY OUT OF THE USE OF THIS SOFTWARE, EVEN IF ADVISED OF THE
00214 * POSSIBILITY OF SUCH DAMAGE.
00215 */
00216
00217 /*****
00218 ** Symbolic names for counter numbers (used in select_p6counter()) **
00219 *****/
00220 *
00221 * These correspond in order to the Pentium Pro counters. Add new counters at
00222 * the end. These agree with the mnemonics in the Pentium Pro Family
00223 * Developer's Manual, vol 3.
00224 *
00225 * Those events marked with a $ require a MESI unit field; those marked with
00226 * a @ require a self/any unit field. Those marked with a 0 are only supported
00227 * in counter 0; those marked with 1 are only supported in counter 1.
00228 */
00229
00230 /* Data cache unit */
00231 #define P6_DATA_MEM_REFS 0x43 /* total memory refs */
00232 #define P6_DCU_LINES_IN 0x45 /* all lines allocated in cache unit */
00233 #define P6_DCU_M_LINES_IN 0x46 /* M lines allocated in cache unit */
00234 #define P6_DCU_M_LINES_OUT 0x47 /* M lines evicted from cache */
00235 #define P6_DCU_MISS_OUTSTANDING 0x48 /* #cycles a miss is outstanding */
00236
00237 /* Instruction fetch unit */
00238 #define P6_IFU_IFETCH 0x80 /* instruction fetches */
00239 #define P6_IFU_IFETCH_MISS 0x81 /* instruction fetch misses */
00240 #define P6_ITLB_MISS 0x85 /* ITLB misses */
00241 #define P6_IFU_MEM_STALL 0x86 /* number of cycles IFU is stalled */
00242 #define P6_ILD_STALL 0x87 /* #stalls in instr length decode */
00243
00244 /* L2 Cache */
00245 #define P6_L2_IFETCH 0x28 /* ($) l2 ifetches */
00246 #define P6_L2_LD 0x29 /* ($) l2 data loads */
00247 #define P6_L2_ST 0x2a /* ($) l2 data stores */
00248 #define P6_L2_LINES_IN 0x24 /* lines allocated in l2 */
00249 #define P6_L2_LINES_OUT 0x26 /* lines removed from l2 */
00250 #define P6_L2_M_LINES_INM 0x25 /* modified lines allocated in l2 */
00251 #define P6_L2_M_LINES_OUTM 0x27 /* modified lines removed from l2 */
00252 #define P6_L2_RQSTS 0x2e /* ($) number of l2 requests */
00253 #define P6_L2_ADS 0x21 /* number of l2 addr strobes */
00254 #define P6_L2_DBUS_BUSY 0x22 /* number of data bus busy cycles */
00255 #define P6_L2_DBUS_BUSY_RD 0x23 /* #bus cycles xferring l2->cpu */
00256
00257 /* External bus logic */
00258 #define P6_BUS_DRDY_CLOCKS 0x62 /* (@) #clocks DRDY is asserted */
00259 #define P6_BUS_LOCK_CLOCKS 0x63 /* (@) #clocks LOCK is asserted */
00260 #define P6_BUS_REQ_OUTSTANDING 0x60 /* #bus requests outstanding */
00261 #define P6_BUS_TRAN_BRD 0x65 /* (@) bus burst read txns */
00262 #define P6_BUS_TRAN_RFO 0x66 /* (@) bus read for ownership txns */
00263 #define P6_BUS_TRAN_WB 0x67 /* (@) bus writeback txns */
00264 #define P6_BUS_TRAN_IFETCH 0x68 /* (@) bus instr fetch txns */
00265 #define P6_BUS_TRAN_INVALID 0x69 /* (@) bus invalidate txns */
00266 #define P6_BUS_TRAN_PWR 0x6a /* (@) bus partial write txns */
00267 #define P6_BUS_TRANS_P 0x6b /* (@) bus partial txns */
00268 #define P6_BUS_TRANS_IO 0x6c /* (@) bus I/O txns */
00269 #define P6_BUS_TRAN_DEF 0x6d /* (@) bus deferred txns */
00270 #define P6_BUS_TRAN_BURST 0x6e /* (@) bus burst txns */
00271 #define P6_BUS_TRAN_ANY 0x70 /* (@) total bus txns */
00272 #define P6_BUS_TRAN_MEM 0x6f /* (@) total memory txns */
00273 #define P6_BUS_DATA_RCV 0x64 /* #busclocks CPU is receiving data */
00274 #define P6_BUS_BNR_DRV 0x61 /* #busclocks CPU is driving BNR pin */
00275 #define P6_BUS_HIT_DRV 0x7a /* #busclocks CPU is driving HIT pin */
00276 #define P6_BUS_HITM_DRV 0x7b /* #busclocks CPU is driving HITM pin */
00277 #define P6_BUS_SNOOP_STALL 0x7e /* #clkcycles bus is snoop-stalled */
00278
00279 /* FPU */
00280 #define P6_FLOPS 0xc1 /* (0) number of FP ops retired */
00281 #define P6_FP_COMP_OPS 0x10 /* (0) computational FPOPS exec'd */
00282 #define P6_FP_ASSIST 0x11 /* (1) FP excep's handled in ucode */
00283 #define P6_MUL 0x12 /* (1) number of FP multiplies */
00284 #define P6_DIV 0x13 /* (1) number of FP divides */
00285 #define P6_CYCLES_DIV_BUSY 0x14 /* (0) number of cycles divider busy */
00286
00287 /* Memory ordering */
00288 #define P6_LD_BLOCKS 0x03 /* number of store buffer blocks */
00289 #define P6_SB_DRAINS 0x04 /* # of store buffer drain cycles */
00290 #define P6_MISALING_MEM_REF 0x05 /* # misaligned data memory refs */
00291
00292 /* Instruction decoding and retirement */
00293 #define P6_INST_RETIRED 0xc0 /* number of instrs retired */
00294 #define P6_UOPS_RETIRED 0xc2 /* number of micro-ops retired */

```



Generated for L4Re by Doxygen

```

00382 : "=g" (*(int *) (res_p)), "=g" (*((int *)res_p)+1)) \
00383 : "g" (cntr) \
00384 : "ecx", "eax", "edx")
00385
00386 static inline l4_uint32_t l4_i686_rdpmc_32(int cntr){
00387     l4_uint32_t x;
00388
00389     __asm__ __volatile__(
00390         ".byte 0xf; .byte 0x33 # RDPMC instruction"
00391         : "=a" (x)
00392         : "c" (cntr)
00393         : "ecx", "eax", "edx");
00394     return x;
00395 }
00396
00397 static inline void l4_i686_select_perfctr_event(int counter,
00398                                             unsigned long long val){
00399     l4_i586_wrmsr(MSR_P6_EVNTSEL0+counter, &val);
00400 }
00401
00402 static inline void l4_i686_select_perfctr0_event(long long *val){
00403     asm volatile(
00404         "movl $MSR_P6_EVNTSEL0, %%ecx\n"
00405         "movl (%%ebx), %%eax\n"
00406         "movl 4(%%ebx), %%edx\n"
00407         /* ".byte 0xcc, 0xeb, 0x01, 0x21\n"
00408         ".byte 0x0f, 0x30\n" // wrmsr
00409         /* ".byte 0xcc, 0xeb, 0x01, 0x21\n"
00410         : /* no output */
00411         : "b" (val)
00412         : "ax", "cx", "dx", "bx"
00413         );
00414
00415 }
00416
00417 /* end of P6 section */
00418 #else
00419
00420 #define K7CNT_U 0x010000 /* Monitor user-level events */
00421 #define K7CNT_K 0x020000 /* Monitor kernel-level events */
00422 #define K7CNT_E 0x040000 /* Edge detect: count state transitions */
00423 #define K7CNT_PC 0x080000 /* Pin control: ?? */
00424 #define K7CNT_IE 0x100000 /* Int enable: enable interrupt on overflow */
00425 #define K7CNT_F 0x200000 /* Freeze counter (handled in software) */
00426 #define K7CNT_EN 0x400000 /* enable counters (in PerfEvtSel0) */
00427 #define K7CNT_IV 0x800000 /* Invert counter mask comparison result */
00428
00429 #define MSR_K7_EVNTSEL0 0xC0010000
00430 #define MSR_K7_EVNTSEL1 0xC0010001
00431 #define MSR_K7_EVNTSEL2 0xC0010002
00432 #define MSR_K7_EVNTSEL3 0xC0010003
00433 #define MSR_K7_PERFCTR0 0xC0010004
00434 #define MSR_K7_PERFCTR1 0xC0010005
00435 #define MSR_K7_PERFCTR2 0xC0010006
00436 #define MSR_K7_PERFCTR3 0xC0010007
00437
00438 #endif
00439
00440 #endif
00441
00442 /* end of P5/P6/K7 section*/
00443 #endif
00444
00445 /* end of not only lib-prototypes section */
00446 #endif
00447
00448 L4_END_DECLS
00449
00450 #endif

```

## 16.78 amd64/l4/util/port\_io.h File Reference

x86 port I/O


```

#include <l4/sys/l4int.h>
#include <l4/sys/compiler.h>
#include <l4/sys/types.h>
#include <l4/sys/utcb.h>

```

```
#include <l4/sys/ipc.h>
```

Include dependency graph for port\_io.h:



## Functions

- `l4_uint8_t l4util_in8 (l4_uint16_t port)`  
*Read byte from I/O port.*
- `l4_uint16_t l4util_in16 (l4_uint16_t port)`  
*Read 16-bit-value from I/O port.*
- `l4_uint32_t l4util_in32 (l4_uint16_t port)`  
*Read 32-bit-value from I/O port.*
- `void l4util_ins8 (l4_uint16_t port, l4_umword_t addr, l4_umword_t count)`  
*Read a block of 8-bit-values from I/O ports.*
- `void l4util_ins16 (l4_uint16_t port, l4_umword_t addr, l4_umword_t count)`  
*Read a block of 16-bit-values from I/O ports.*
- `void l4util_ins32 (l4_uint16_t port, l4_umword_t addr, l4_umword_t count)`  
*Read a block of 32-bit-values from I/O ports.*
- `void l4util_out8 (l4_uint8_t value, l4_uint16_t port)`  
*Write byte to I/O port.*
- `void l4util_out16 (l4_uint16_t value, l4_uint16_t port)`  
*Write 16-bit-value to I/O port.*
- `void l4util_out32 (l4_uint32_t value, l4_uint16_t port)`  
*Write 32-bit-value to I/O port.*
- `void l4util_outs8 (l4_uint16_t port, l4_umword_t addr, l4_umword_t count)`  
*Write a block of bytes to I/O port.*
- `void l4util_outs16 (l4_uint16_t port, l4_umword_t addr, l4_umword_t count)`  
*Write a block of 16-bit-values to I/O port.*
- `void l4util_outs32 (l4_uint16_t port, l4_umword_t addr, l4_umword_t count)`  
*Write block of 32-bit-values to I/O port.*
- `void l4util_iodelay (void)`  
*delay I/O port access by writing to port 0x80*
- `int l4util_ioport_map (l4_cap_idx_t sigma0id, unsigned port_start, unsigned log2size)`  
*Map a range of I/O ports.*

## 16.78.1 Detailed Description

x86 port I/O

Date

06/2003

Author

Frank Mehnert [fm3@os.inf.tu-dresden.de](mailto:fm3@os.inf.tu-dresden.de)

Definition in file [port\\_io.h](#).

## 16.79 port\_io.h

[Go to the documentation of this file.](#)

```

00001 /*****
00009 /*****
00010
00011 */
00012 * (c) 2003-2009 Author(s)
00013 *     economic rights: Technische Universität Dresden (Germany)
00014 * License: see LICENSE.spdx (in this directory or the directories above)
00015 */
00016
00017 #ifndef _L4UTIL_PORT_IO_H
00018 #define _L4UTIL_PORT_IO_H
00019
00024
00025 /* L4 includes */
00026 #include <l4/sys/l4int.h>
00027 #include <l4/sys/compiler.h>
00028 #include <l4/sys/types.h>
00029
00030 /*****
00031 *** Prototypes
00032 *****/
00033
00034 L4_BEGIN_DECLS
00045 L4_INLINE l4_uint8_t
00046 l4util_in8(l4_uint16_t port);
00047
00054 L4_INLINE l4_uint16_t
00055 l4util_in16(l4_uint16_t port);
00056
00063 L4_INLINE l4_uint32_t
00064 l4util_in32(l4_uint16_t port);
00065
00073 L4_INLINE void
00074 l4util_ins8(l4_uint16_t port, l4_umword_t addr, l4_umword_t count);
00075
00083 L4_INLINE void
00084 l4util_ins16(l4_uint16_t port, l4_umword_t addr, l4_umword_t count);
00085
00093 L4_INLINE void
00094 l4util_ins32(l4_uint16_t port, l4_umword_t addr, l4_umword_t count);
00095
00102 L4_INLINE void
00103 l4util_out8(l4_uint8_t value, l4_uint16_t port);
00104
00111 L4_INLINE void
00112 l4util_out16(l4_uint16_t value, l4_uint16_t port);
00113
00120 L4_INLINE void
00121 l4util_out32(l4_uint32_t value, l4_uint16_t port);
00122
00130 L4_INLINE void
00131 l4util_outs8(l4_uint16_t port, l4_umword_t addr, l4_umword_t count);
00132
00140 L4_INLINE void
00141 l4util_outs16(l4_uint16_t port, l4_umword_t addr, l4_umword_t count);

```

```

00142
00150 L4_INLINE void
00151 l4util_outs32(l4_uint16_t port, l4_umword_t addr, l4_umword_t count);
00152
00156 L4_INLINE void
00157 l4util_iodelay(void);
00158
00170 L4_INLINE int
00171 l4util_ioport_map(l4_cap_idx_t sigma0id,
00172                  unsigned port_start, unsigned log2size);
00173
00175
00176 L4_END_DECLS
00177
00178
00179 /***** Implementation *****/
00180 *** Implementation
00181 *****/
00182
00183 #include <l4/sys/utcb.h>
00184 #include <l4/sys/ipc.h>
00185
00186 L4_INLINE l4_uint8_t
00187 l4util_in8(l4_uint16_t port)
00188 {
00189     l4_uint8_t value;
00190     asm volatile ("inb %w1, %b0" : "=a" (value) : "Nd" (port));
00191     return value;
00192 }
00193
00194 L4_INLINE l4_uint16_t
00195 l4util_in16(l4_uint16_t port)
00196 {
00197     l4_uint16_t value;
00198     asm volatile ("inw %w1, %w0" : "=a" (value) : "Nd" (port));
00199     return value;
00200 }
00201
00202 L4_INLINE l4_uint32_t
00203 l4util_in32(l4_uint16_t port)
00204 {
00205     l4_uint32_t value;
00206     asm volatile ("inl %w1, %0" : "=a" (value) : "Nd" (port));
00207     return value;
00208 }
00209
00210 L4_INLINE void
00211 l4util_ins8(l4_uint16_t port, l4_umword_t addr, l4_umword_t count)
00212 {
00213     l4_umword_t dummy1, dummy2;
00214     asm volatile ("rep insb" : "=D" (dummy1), "=c" (dummy2)
00215                  : "d" (port), "D" (addr), "c" (count)
00216                  : "memory");
00217 }
00218
00219 L4_INLINE void
00220 l4util_ins16(l4_uint16_t port, l4_umword_t addr, l4_umword_t count)
00221 {
00222     l4_umword_t dummy1, dummy2;
00223     asm volatile ("rep insw" : "=D" (dummy1), "=c" (dummy2)
00224                  : "d" (port), "D" (addr), "c" (count)
00225                  : "memory");
00226 }
00227
00228 L4_INLINE void
00229 l4util_ins32(l4_uint16_t port, l4_umword_t addr, l4_umword_t count)
00230 {
00231     l4_umword_t dummy1, dummy2;
00232     asm volatile ("rep insl" : "=D" (dummy1), "=c" (dummy2)
00233                  : "d" (port), "D" (addr), "c" (count)
00234                  : "memory");
00235 }
00236
00237 L4_INLINE void
00238 l4util_out8(l4_uint8_t value, l4_uint16_t port)
00239 {
00240     asm volatile ("outb %b0, %w1" : : "a" (value), "Nd" (port));
00241 }
00242
00243 L4_INLINE void
00244 l4util_out16(l4_uint16_t value, l4_uint16_t port)
00245 {
00246     asm volatile ("outw %w0, %w1" : : "a" (value), "Nd" (port));
00247 }
00248
00249 L4_INLINE void
00250 l4util_out32(l4_uint32_t value, l4_uint16_t port)

```

```

00251 {
00252     asm volatile ("outl %0, %w1" : : "a" (value), "Nd" (port));
00253 }
00254
00255 L4_INLINE void
00256 l4util_outs8(l4_uint16_t port, l4_umword_t addr, l4_umword_t count)
00257 {
00258     l4_umword_t dummy1, dummy2;
00259     asm volatile ("rep outsb" : "=S"(dummy1), "=c"(dummy2)
00260                  : "d" (port), "S" (addr), "c"(count)
00261                  : "memory");
00262 }
00263
00264 L4_INLINE void
00265 l4util_outs16(l4_uint16_t port, l4_umword_t addr, l4_umword_t count)
00266 {
00267     l4_umword_t dummy1, dummy2;
00268     asm volatile ("rep outsw" : "=S"(dummy1), "=c"(dummy2)
00269                  : "d" (port), "S" (addr), "c"(count)
00270                  : "memory");
00271 }
00272
00273 L4_INLINE void
00274 l4util_outs32(l4_uint16_t port, l4_umword_t addr, l4_umword_t count)
00275 {
00276     l4_umword_t dummy1, dummy2;
00277     asm volatile ("rep outsl" : "=S"(dummy1), "=c"(dummy2)
00278                  : "d" (port), "S" (addr), "c"(count)
00279                  : "memory");
00280 }
00281
00282 L4_INLINE void
00283 l4util_iodelay(void)
00284 {
00285     asm volatile ("outb %a1,$0x80");
00286 }
00287
00288 L4_INLINE int
00289 l4util_ioport_map(l4_cap_idx_t sigma0id,
00290                  unsigned port_start, unsigned log2size)
00291 {
00292     l4_fpage_t iofp;
00293     l4_msgtag_t tag;
00294     long err;
00295
00296     iofp = l4_iofpage(port_start, log2size);
00297     l4_utcb_mr()->mr[0] = iofp.raw;
00298     l4_utcb_br()->bdr = 0;
00299     l4_utcb_br()->br[0] = L4_ITEM_MAP;
00300     l4_utcb_br()->br[1] = iofp.raw;
00301     tag = l4_ipc_call(sigma0id, l4_utcb(),
00302                      l4_msgtag(L4_PROTO_IO_PAGE_FAULT, 1, 0, 0),
00303                      L4_IPC_NEVER);
00304
00305     if ((err = l4_ipc_error(tag, l4_utcb())))
00306         return err;
00307
00308     return l4_msgtag_items(tag) > 0 ? 0 : -L4_ENOENT;
00309 }
00310
00311 #endif

```

## 16.80 x86/l4/util/port\_io.h File Reference


x86 port I/O

```

#include <l4/sys/l4int.h>
#include <l4/sys/compiler.h>
#include <l4/sys/types.h>
#include <l4/sys/utcb.h>
#include <l4/sys/ipc.h>

```

Include dependency graph for port\_io.h:



## Functions

- [i4\\_uint8\\_t i4util\\_in8 \(i4\\_uint16\\_t port\)](#)  
*Read byte from I/O port.*
- [i4\\_uint16\\_t i4util\\_in16 \(i4\\_uint16\\_t port\)](#)  
*Read 16-bit-value from I/O port.*
- [i4\\_uint32\\_t i4util\\_in32 \(i4\\_uint16\\_t port\)](#)  
*Read 32-bit-value from I/O port.*
- [void i4util\\_ins8 \(i4\\_uint16\\_t port, i4\\_umword\\_t addr, i4\\_umword\\_t count\)](#)  
*Read a block of 8-bit-values from I/O ports.*
- [void i4util\\_ins16 \(i4\\_uint16\\_t port, i4\\_umword\\_t addr, i4\\_umword\\_t count\)](#)  
*Read a block of 16-bit-values from I/O ports.*
- [void i4util\\_ins32 \(i4\\_uint16\\_t port, i4\\_umword\\_t addr, i4\\_umword\\_t count\)](#)  
*Read a block of 32-bit-values from I/O ports.*
- [void i4util\\_out8 \(i4\\_uint8\\_t value, i4\\_uint16\\_t port\)](#)  
*Write byte to I/O port.*
- [void i4util\\_out16 \(i4\\_uint16\\_t value, i4\\_uint16\\_t port\)](#)  
*Write 16-bit-value to I/O port.*
- [void i4util\\_out32 \(i4\\_uint32\\_t value, i4\\_uint16\\_t port\)](#)  
*Write 32-bit-value to I/O port.*
- [void i4util\\_outs8 \(i4\\_uint16\\_t port, i4\\_umword\\_t addr, i4\\_umword\\_t count\)](#)  
*Write a block of bytes to I/O port.*
- [void i4util\\_outs16 \(i4\\_uint16\\_t port, i4\\_umword\\_t addr, i4\\_umword\\_t count\)](#)  
*Write a block of 16-bit-values to I/O port.*
- [void i4util\\_outs32 \(i4\\_uint16\\_t port, i4\\_umword\\_t addr, i4\\_umword\\_t count\)](#)  
*Write block of 32-bit-values to I/O port.*
- [void i4util\\_iodelay \(void\)](#)  
*delay I/O port access by writing to port 0x80*
- [int i4util\\_ioport\\_map \(i4\\_cap\\_idx\\_t sigma0id, unsigned port\\_start, unsigned log2size\)](#)  
*Map a range of I/O ports.*

## 16.80.1 Detailed Description

x86 port I/O

Date

06/2003

Author

Frank Mehnert [fm3@os.inf.tu-dresden.de](mailto:fm3@os.inf.tu-dresden.de)

Definition in file [port\\_io.h](#).

## 16.81 port\_io.h

[Go to the documentation of this file.](#)

```

00001  /*****
00009  /*****
00010
00011  /*
00012   * (c) 2003-2009 Author(s)
00013   *     economic rights: Technische Universität Dresden (Germany)
00014   * License: see LICENSE.spdx (in this directory or the directories above)
00015   */
00016
00017 #ifndef _L4UTIL_PORT_IO_H
00018 #define _L4UTIL_PORT_IO_H
00019
00024
00025 /* L4 includes */
00026 #include <l4/sys/l4int.h>
00027 #include <l4/sys/compiler.h>
00028 #include <l4/sys/types.h>
00029
00030 /*****
00031  *** Prototypes
00032  *****/
00033
00034 L4_BEGIN_DECLS
00045 L4_INLINE l4_uint8_t
00046 l4util_in8(l4_uint16_t port);
00047
00054 L4_INLINE l4_uint16_t
00055 l4util_in16(l4_uint16_t port);
00056
00063 L4_INLINE l4_uint32_t
00064 l4util_in32(l4_uint16_t port);
00065
00073 L4_INLINE void
00074 l4util_ins8(l4_uint16_t port, l4_umword_t addr, l4_umword_t count);
00075
00083 L4_INLINE void
00084 l4util_ins16(l4_uint16_t port, l4_umword_t addr, l4_umword_t count);
00085
00093 L4_INLINE void
00094 l4util_ins32(l4_uint16_t port, l4_umword_t addr, l4_umword_t count);
00095
00102 L4_INLINE void
00103 l4util_out8(l4_uint8_t value, l4_uint16_t port);
00104
00111 L4_INLINE void
00112 l4util_out16(l4_uint16_t value, l4_uint16_t port);
00113
00120 L4_INLINE void
00121 l4util_out32(l4_uint32_t value, l4_uint16_t port);
00122
00130 L4_INLINE void
00131 l4util_outs8(l4_uint16_t port, l4_umword_t addr, l4_umword_t count);
00132
00140 L4_INLINE void
00141 l4util_outs16(l4_uint16_t port, l4_umword_t addr, l4_umword_t count);

```



```

00142
00150 L4_INLINE void
00151 l4util_outs32(l4_uint16_t port, l4_umword_t addr, l4_umword_t count);
00152
00156 L4_INLINE void
00157 l4util_iodelay(void);
00158
00170 L4_INLINE int
00171 l4util_ioport_map(l4_cap_idx_t sigma0id,
00172                  unsigned port_start, unsigned log2size);
00173
00175
00176 L4_END_DECLS
00177
00178
00179 /***** Implementation *****/
00180 *** Implementation
00181 *****/
00182
00183 #include <l4/sys/utcb.h>
00184 #include <l4/sys/ipc.h>
00185
00186 L4_INLINE l4_uint8_t
00187 l4util_in8(l4_uint16_t port)
00188 {
00189     l4_uint8_t value;
00190     asm volatile ("inb %w1, %b0" : "=a" (value) : "Nd" (port));
00191     return value;
00192 }
00193
00194 L4_INLINE l4_uint16_t
00195 l4util_in16(l4_uint16_t port)
00196 {
00197     l4_uint16_t value;
00198     asm volatile ("inw %w1, %w0" : "=a" (value) : "Nd" (port));
00199     return value;
00200 }
00201
00202 L4_INLINE l4_uint32_t
00203 l4util_in32(l4_uint16_t port)
00204 {
00205     l4_uint32_t value;
00206     asm volatile ("inl %w1, %0" : "=a" (value) : "Nd" (port));
00207     return value;
00208 }
00209
00210 L4_INLINE void
00211 l4util_ins8(l4_uint16_t port, l4_umword_t addr, l4_umword_t count)
00212 {
00213     l4_umword_t dummy1, dummy2;
00214     asm volatile ("rep insb" : "=D" (dummy1), "=c" (dummy2)
00215                  : "d" (port), "D" (addr), "c" (count)
00216                  : "memory");
00217 }
00218
00219 L4_INLINE void
00220 l4util_ins16(l4_uint16_t port, l4_umword_t addr, l4_umword_t count)
00221 {
00222     l4_umword_t dummy1, dummy2;
00223     asm volatile ("rep insw" : "=D" (dummy1), "=c" (dummy2)
00224                  : "d" (port), "D" (addr), "c" (count)
00225                  : "memory");
00226 }
00227
00228 L4_INLINE void
00229 l4util_ins32(l4_uint16_t port, l4_umword_t addr, l4_umword_t count)
00230 {
00231     l4_umword_t dummy1, dummy2;
00232     asm volatile ("rep insl" : "=D" (dummy1), "=c" (dummy2)
00233                  : "d" (port), "D" (addr), "c" (count)
00234                  : "memory");
00235 }
00236
00237 L4_INLINE void
00238 l4util_out8(l4_uint8_t value, l4_uint16_t port)
00239 {
00240     asm volatile ("outb %b0, %w1" : : "a" (value), "Nd" (port));
00241 }
00242
00243 L4_INLINE void
00244 l4util_out16(l4_uint16_t value, l4_uint16_t port)
00245 {
00246     asm volatile ("outw %w0, %w1" : : "a" (value), "Nd" (port));
00247 }
00248
00249 L4_INLINE void
00250 l4util_out32(l4_uint32_t value, l4_uint16_t port)

```

```

00251 {
00252     asm volatile ("outl %0, %w1" : : "a" (value), "Nd" (port));
00253 }
00254
00255 L4_INLINE void
00256 l4util_outs8(l4_uint16_t port, l4_umword_t addr, l4_umword_t count)
00257 {
00258     l4_umword_t dummy1, dummy2;
00259     asm volatile ("rep outsb" : "=S"(dummy1), "=c"(dummy2)
00260                  : "d" (port), "S" (addr), "c"(count)
00261                  : "memory");
00262 }
00263
00264 L4_INLINE void
00265 l4util_outs16(l4_uint16_t port, l4_umword_t addr, l4_umword_t count)
00266 {
00267     l4_umword_t dummy1, dummy2;
00268     asm volatile ("rep outsw" : "=S"(dummy1), "=c"(dummy2)
00269                  : "d" (port), "S" (addr), "c"(count)
00270                  : "memory");
00271 }
00272
00273 L4_INLINE void
00274 l4util_outs32(l4_uint16_t port, l4_umword_t addr, l4_umword_t count)
00275 {
00276     l4_umword_t dummy1, dummy2;
00277     asm volatile ("rep outsl" : "=S"(dummy1), "=c"(dummy2)
00278                  : "d" (port), "S" (addr), "c"(count)
00279                  : "memory");
00280 }
00281
00282 L4_INLINE void
00283 l4util_iodelay(void)
00284 {
00285     asm volatile ("outb %a1, $0x80");
00286 }
00287
00288 L4_INLINE int
00289 l4util_ioport_map(l4_cap_idx_t sigma0id,
00290                  unsigned port_start, unsigned log2size)
00291 {
00292     l4_fpage_t iofp;
00293     l4_msgtag_t tag;
00294     long err;
00295
00296     iofp = l4_iofpage(port_start, log2size);
00297     l4_utcb_mr()->mr[0] = iofp.raw;
00298     l4_utcb_br()->bdr = 0;
00299     l4_utcb_br()->br[0] = L4_ITEM_MAP;
00300     l4_utcb_br()->br[1] = iofp.raw;
00301     tag = l4_ipc_call(sigma0id, l4_utcb(),
00302                     l4_msgtag(L4_PROTO_IO_PAGE_FAULT, 1, 0, 0),
00303                     L4_IPC_NEVER);
00304
00305     if ((err = l4_ipc_error(tag, l4_utcb())))
00306         return err;
00307
00308     return l4_msgtag_items(tag) > 0 ? 0 : -L4_ENOENT;
00309 }
00310
00311 #endif

```

## 16.82 amd64/l4/util/rdtsc.h File Reference


Timestamp counter related functions.

```

#include <l4/sys/compiler.h>
#include <l4/sys/l4int.h>
#include <l4/sys/kip.h>

```

Include dependency graph for rdtsc.h:



## Functions

- `l4_cpu_time_t l4_rdtsc` (void)  
Read current value of CPU-internal timestamp counter.
- `l4_uint32_t l4_rdtsc_32` (void)  
Read the lest significant 32 bit of the TSC.
- `l4_uint64_t l4_rdpmc` (int ecx)  
Return current value of CPU-internal performance measurement counter.
- `l4_uint32_t l4_rdpmc_32` (int ecx)  
Return the least significant 32 bit of a performance counter.
- `l4_uint64_t l4_tsc_to_ns` (`l4_cpu_time_t` tsc)  
Convert timestamp to ns value.
- `l4_uint64_t l4_tsc_to_us` (`l4_cpu_time_t` tsc)  
Convert timestamp into micro seconds value.
- `void l4_tsc_to_s_and_ns` (`l4_cpu_time_t` tsc, `l4_uint32_t` \*s, `l4_uint32_t` \*ns)  
Convert timestamp to s.ns value.
- `l4_cpu_time_t l4_ns_to_tsc` (`l4_uint64_t` ns)  
Convert nano seconds into CPU ticks.
- `void l4_busy_wait_ns` (`l4_uint64_t` ns)  
Wait busy for a small amount of time.
- `void l4_busy_wait_us` (`l4_uint64_t` us)  
Wait busy for a small amount of time.
- `l4_uint32_t l4_calibrate_tsc` (`l4_kernel_info_t` const \*kip)  
Determine scalers for timestamp calculations.
- `l4_uint32_t l4_tsc_init` (`l4_kernel_info_t` const \*kip)  
Initialize scaler for TSC calibrations from the kernel.
- `l4_uint32_t l4_get_hz` (void)  
Get CPU frequency in Hz.

## 16.82.1 Detailed Description

Timestamp counter related functions.

### Author

Frank Mehnert [fm3@os.inf.tu-dresden.de](mailto:fm3@os.inf.tu-dresden.de)

Definition in file [rdtsc.h](#).

## 16.83 rdtsc.h

[Go to the documentation of this file.](#)

```

00001
00008
00009 /*
00010  * (c) 2003-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00011  *      Alexander Warg <warg@os.inf.tu-dresden.de>,
00012  *      Torsten Frenzel <frenzel@os.inf.tu-dresden.de>
00013  *      economic rights: Technische Universität Dresden (Germany)
00014  * License: see LICENSE.spdx (in this directory or the directories above)
00015  */
00016
00017 #ifndef __l4_rdtsc_h
00018 #define __l4_rdtsc_h
00019
00024
00025 #include <l4/sys/compiler.h>
00026 #include <l4/sys/l4int.h>
00027 #include <l4/sys/kip.h>
00028
00029 L4_BEGIN_DECLS
00030
00031 /* interface */
00036
00037 extern l4_uint32_t l4_scaler_tsc_to_ns;
00038 extern l4_uint32_t l4_scaler_tsc_to_us;
00039 extern l4_uint32_t l4_scaler_ns_to_tsc;
00040 extern l4_uint32_t l4_scaler_tsc_linux;
00041
00046 L4_INLINE l4_cpu_time_t
00047 l4_rdtsc (void);
00048
00054 L4_INLINE
00055 l4_uint32_t l4_rdtsc_32 (void);
00056
00063 L4_INLINE l4_uint64_t
00064 l4_rdpmc (int ecx);
00065
00071 L4_INLINE
00072 l4_uint32_t l4_rdpmc_32 (int ecx);
00073
00078 L4_INLINE l4_uint64_t
00079 l4_tsc_to_ns (l4_cpu_time_t tsc);
00080
00085 L4_INLINE l4_uint64_t
00086 l4_tsc_to_us (l4_cpu_time_t tsc);
00087
00093 L4_INLINE void
00094 l4_tsc_to_s_and_ns (l4_cpu_time_t tsc, l4_uint32_t *s, l4_uint32_t *ns);
00095
00101 L4_INLINE l4_cpu_time_t
00102 l4_ns_to_tsc (l4_uint64_t ns);
00103
00109 L4_INLINE void
00110 l4_busy_wait_ns (l4_uint64_t ns);
00111
00117 L4_INLINE void
00118 l4_busy_wait_us (l4_uint64_t us);
00119
00126 L4_INLINE l4_uint32_t
00127 l4_calibrate_tsc (l4_kernel_info_t const *kip);
00128
00142 L4_CV l4_uint32_t
00143 l4_tsc_init (l4_kernel_info_t const *kip);

```

```

00144
00149 L4_CV l4_uint32_t
00150 l4_get_hz (void);
00151
00153
00154 L4_END_DECLS
00155
00156 /* implementation */
00157
00158 L4_INLINE l4_uint32_t
00159 l4_calibrate_tsc(l4_kernel_info_t const *kip)
00160 {
00161     return l4_tsc_init(kip);
00162 }
00163
00164 L4_INLINE l4_cpu_time_t
00165 l4_rdtsc (void)
00166 {
00167     l4_umword_t lo, hi;
00168
00169     __asm__ __volatile__ ("rdtsc" : "=a"(lo), "=d"(hi));
00170
00171     return ((l4_cpu_time_t)hi << 32) | lo;
00172 }
00173
00174 L4_INLINE l4_uint64_t
00175 l4_rdpmc (int ecx)
00176 {
00177     l4_umword_t lo, hi;
00178
00179     __asm__ __volatile__ ("rdpmc" : "=a"(lo), "=d"(hi) : "c"(ecx));
00180
00181     return ((l4_cpu_time_t)hi << 32) | lo;
00182 }
00183
00184 L4_INLINE
00185 l4_uint32_t l4_rdtsc_32(void)
00186 {
00187     l4_umword_t lo, hi;
00188
00189     __asm__ __volatile__ ("rdtsc" : "=a"(lo), "=d"(hi));
00190
00191     return lo;
00192 }
00193
00194 L4_INLINE
00195 l4_uint32_t l4_rdpmc_32(int ecx)
00196 {
00197     l4_umword_t lo, hi;
00198
00199     __asm__ __volatile__ ("rdpmc" : "=a"(lo), "=d"(hi) : "c"(ecx));
00200
00201     return lo;
00202 }
00203
00204 L4_INLINE l4_uint64_t
00205 l4_tsc_to_ns (l4_cpu_time_t tsc)
00206 {
00207     l4_uint64_t ns, dummy;
00208     __asm__
00209     ("
00210      \"mulq  %3      \n\t\"
00211      \"shrd  $27, %%rdx, %%rax      \n\t\"
00212      :\"=a\" (ns), \"=d\"(dummy)
00213      :\"a\" (tsc), \"r\" ((l4_uint64_t)l4_scaler_tsc_to_ns)
00214      );
00215     return ns;
00216 }
00217
00218 L4_INLINE l4_uint64_t
00219 l4_tsc_to_us (l4_cpu_time_t tsc)
00220 {
00221     l4_uint64_t ns, dummy;
00222     __asm__
00223     ("
00224      \"mulq  %3      \n\t\"
00225      \"shrd  $32, %%rdx, %%rax      \n\t\"
00226      :\"=a\" (ns), \"=d\" (dummy)
00227      :\"a\" (tsc), \"r\" ((l4_uint64_t)l4_scaler_tsc_to_us)
00228      );
00229     return ns;
00230 }
00231
00232 L4_INLINE void
00233 l4_tsc_to_s_and_ns (l4_cpu_time_t tsc, l4_uint32_t *s, l4_uint32_t *ns)
00234 {
00235     __asm__

```

```

00236     ("      \n\t"
00237     "mulq  %3      \n\t"
00238     "shrd  $27, %%rdx, %%rax      \n\t"
00239     "xorq  %%rdx, %%rdx      \n\t"
00240     "divq  %4      \n\t"
00241     : "=a" (*s), "=d" (*ns)
00242     : "a" (tsc), "r" ((l4_uint64_t)l4_scaler_tsc_to_ns),
00243     "rm"(1000000000ULL)
00244     );
00245 }
00246
00247 L4_INLINE l4_cpu_time_t
00248 l4_ns_to_tsc (l4_uint64_t ns)
00249 {
00250     l4_uint64_t tsc, dummy;
00251     __asm__
00252     ("      \n\t"
00253     "mulq  %3      \n\t"
00254     "shrd  $27, %%rdx, %%rax      \n\t"
00255     : "=a" (tsc), "=d" (dummy)
00256     : "a" (ns), "r" ((l4_uint64_t)l4_scaler_ns_to_tsc)
00257     );
00258     return tsc;
00259 }
00260
00261 L4_INLINE void
00262 l4_busy_wait_ns (l4_uint64_t ns)
00263 {
00264     l4_cpu_time_t stop = l4_rdtsc();
00265     stop += l4_ns_to_tsc(ns);
00266
00267     while (l4_rdtsc() < stop)
00268         ;
00269 }
00270
00271 L4_INLINE void
00272 l4_busy_wait_us (l4_uint64_t us)
00273 {
00274     l4_cpu_time_t stop = l4_rdtsc ();
00275     stop += l4_ns_to_tsc(us*1000ULL);
00276
00277     while (l4_rdtsc() < stop)
00278         ;
00279 }
00280
00281 #endif /* __l4_rdtsc_h */
00282

```

## 16.84 x86/i4/util/rdtsc.h File Reference


Timestamp counter related functions.

```

#include <l4/sys/compiler.h>
#include <l4/sys/l4int.h>
#include <l4/sys/kip.h>

```

Include dependency graph for rdtsc.h:



## Functions

- `l4_cpu_time_t l4_rdtsc` (void)  
Read current value of CPU-internal timestamp counter.
- `l4_uint32_t l4_rdtsc_32` (void)  
Read the least significant 32 bit of the TSC.
- `l4_uint64_t l4_rdpmc` (int ecx)  
Return current value of CPU-internal performance measurement counter.
- `l4_uint32_t l4_rdpmc_32` (int ecx)  
Return the least significant 32 bit of a performance counter.
- `l4_uint64_t l4_tsc_to_ns` (`l4_cpu_time_t` tsc)  
Convert timestamp to ns value.
- `l4_uint64_t l4_tsc_to_us` (`l4_cpu_time_t` tsc)  
Convert timestamp into micro seconds value.
- `void l4_tsc_to_s_and_ns` (`l4_cpu_time_t` tsc, `l4_uint32_t` \*s, `l4_uint32_t` \*ns)  
Convert timestamp to s.ns value.
- `l4_cpu_time_t l4_ns_to_tsc` (`l4_uint64_t` ns)  
Convert nano seconds into CPU ticks.
- `void l4_busy_wait_ns` (`l4_uint64_t` ns)  
Wait busy for a small amount of time.
- `void l4_busy_wait_us` (`l4_uint64_t` us)  
Wait busy for a small amount of time.
- `l4_uint32_t l4_calibrate_tsc` (`l4_kernel_info_t` const \*kip)  
Determine scalars for timestamp calculations.
- `l4_uint32_t l4_tsc_init` (`l4_kernel_info_t` const \*kip)  
Initialize scaler for TSC calibrations from the kernel.
- `l4_uint32_t l4_get_hz` (void)  
Get CPU frequency in Hz.

## 16.84.1 Detailed Description

Timestamp counter related functions.

### Author

Frank Mehnert [fm3@os.inf.tu-dresden.de](mailto:fm3@os.inf.tu-dresden.de)

Definition in file [rdtsc.h](#).

## 16.85 rdtsc.h

[Go to the documentation of this file.](#)

```

00001
00008
00009 /*
00010  * (c) 2003-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00011  *      Alexander Warg <warg@os.inf.tu-dresden.de>,
00012  *      Frank Mehnert <fm3@os.inf.tu-dresden.de>,
00013  *      Jork Löser <jork@os.inf.tu-dresden.de>,
00014  *      Martin Pohlack <mp26@os.inf.tu-dresden.de>
00015  *      economic rights: Technische Universität Dresden (Germany)
00016  * License: see LICENSE.spdx (in this directory or the directories above)
00017  */
00018
00019 #ifndef __l4_rdtsc_h
00020 #define __l4_rdtsc_h
00021
00026
00027 #include <l4/sys/compiler.h>
00028 #include <l4/sys/l4int.h>
00029 #include <l4/sys/kip.h>
00030
00031 L4_BEGIN_DECLS
00032
00033 /* interface */
00038
00039 extern l4_uint32_t l4_scaler_tsc_to_ns;
00040 extern l4_uint32_t l4_scaler_tsc_to_us;
00041 extern l4_uint32_t l4_scaler_ns_to_tsc;
00042 extern l4_uint32_t l4_scaler_tsc_linux;
00043
00048 L4_INLINE l4_cpu_time_t
00049 l4_rdtsc (void);
00050
00056 L4_INLINE
00057 l4_uint32_t l4_rdtsc_32 (void);
00058
00065 L4_INLINE l4_uint64_t
00066 l4_rdpmc (int ecx);
00067
00073 L4_INLINE
00074 l4_uint32_t l4_rdpmc_32 (int ecx);
00075
00080 L4_INLINE l4_uint64_t
00081 l4_tsc_to_ns (l4_cpu_time_t tsc);
00082
00087 L4_INLINE l4_uint64_t
00088 l4_tsc_to_us (l4_cpu_time_t tsc);
00089
00095 L4_INLINE void
00096 l4_tsc_to_s_and_ns (l4_cpu_time_t tsc, l4_uint32_t *s, l4_uint32_t *ns);
00097
00103 L4_INLINE l4_cpu_time_t
00104 l4_ns_to_tsc (l4_uint64_t ns);
00105
00111 L4_INLINE void
00112 l4_busy_wait_ns (l4_uint64_t ns);
00113
00119 L4_INLINE void
00120 l4_busy_wait_us (l4_uint64_t us);
00121
00128 L4_INLINE l4_uint32_t
00129 l4_calibrate_tsc (l4_kernel_info_t const *kip);
00130

```



```

00144 L4_CV l4_uint32_t
00145 l4_tsc_init(l4_kernel_info_t const *kip);
00146
00151 L4_CV l4_uint32_t
00152 l4_get_hz (void);
00153
00155
00156 L4_END_DECLS
00157
00158 /* implementation */
00159
00160 L4_INLINE l4_uint32_t
00161 l4_calibrate_tsc(l4_kernel_info_t const *kip)
00162 {
00163     return l4_tsc_init(kip);
00164 }
00165
00166 L4_INLINE l4_cpu_time_t
00167 l4_rdtsc (void)
00168 {
00169     l4_cpu_time_t v;
00170
00171     __asm__ __volatile__ (
00172         ("    \n\t"
00173          ".byte 0x0f, 0x31    \n\t"
00174          /*"rdtsc\n\t"*/
00175          :
00176          "=A" (v)
00177          : /* no inputs */
00178          );
00179
00180     return v;
00181 }
00182
00183 /* the same, but only 32 bit. Useful for smaller differences,
00184    needs less cycles. */
00185 L4_INLINE
00186 l4_uint32_t l4_rdtsc_32(void)
00187 {
00188     l4_uint32_t x;
00189
00190     __asm__ __volatile__ (
00191         ".byte 0x0f, 0x31\n\t" // rdtsc
00192         : "=a" (x)
00193         :
00194         : "edx");
00195
00196     return x;
00197 }
00198
00199 L4_INLINE l4_uint64_t
00200 l4_rdpmc (int ecx)
00201 {
00202     l4_cpu_time_t v;
00203
00204     __asm__ __volatile__ (
00205         "rdpmc    \n\t"
00206         :
00207         "=A" (v)
00208         : "c" (ecx)
00209         );
00210
00211     return v;
00212 }
00213
00214 /* the same, but only 32 bit. Useful for smaller differences,
00215    needs less cycles. */
00216 L4_INLINE
00217 l4_uint32_t l4_rdpmc_32(int ecx)
00218 {
00219     l4_uint32_t x;
00220
00221     __asm__ __volatile__ (
00222         "rdpmc    \n\t"
00223         : "=a" (x)
00224         : "c" (ecx)
00225         : "edx");
00226
00227     return x;
00228 }
00229
00230 L4_INLINE l4_uint64_t
00231 l4_tsc_to_ns (l4_cpu_time_t tsc)
00232 {
00233     l4_uint32_t dummy;
00234     l4_uint64_t ns;
00235     __asm__

```

```

00236 ("      \n\t"
00237 "movl %%edx, %%ecx \n\t"
00238 "mull %3 \n\t"
00239 "movl %%ecx, %%eax \n\t"
00240 "movl %%edx, %%ecx \n\t"
00241 "mull %3 \n\t"
00242 "addl %%ecx, %%eax \n\t"
00243 "adcl $0, %%edx \n\t"
00244 "shld $5, %%eax, %%edx \n\t"
00245 "shll $5, %%eax \n\t"
00246 : "=A" (ns),
00247 "=&c" (dummy)
00248 : "0" (tsc),
00249 "g" (l4_scaler_tsc_to_ns)
00250 );
00251 return ns;
00252 }
00253
00254 L4_INLINE l4_uint64_t
00255 l4_tsc_to_us (l4_cpu_time_t tsc)
00256 {
00257     l4_uint32_t dummy;
00258     l4_uint64_t us;
00259     __asm__
00260 ("      \n\t"
00261 "movl %%edx, %%ecx \n\t"
00262 "mull %3 \n\t"
00263 "movl %%ecx, %%eax \n\t"
00264 "movl %%edx, %%ecx \n\t"
00265 "mull %3 \n\t"
00266 "addl %%ecx, %%eax \n\t"
00267 "adcl $0, %%edx \n\t"
00268 : "=A" (us),
00269 "=&c" (dummy)
00270 : "0" (tsc),
00271 "g" (l4_scaler_tsc_to_us)
00272 );
00273 return us;
00274 }
00275
00276 L4_INLINE void
00277 l4_tsc_to_s_and_ns (l4_cpu_time_t tsc, l4_uint32_t *s, l4_uint32_t *ns)
00278 {
00279     l4_uint32_t dummy;
00280     __asm__
00281 ("      \n\t"
00282 "movl %%edx, %%ecx \n\t"
00283 "mull %4 \n\t"
00284 "movl %%ecx, %%eax \n\t"
00285 "movl %%edx, %%ecx \n\t"
00286 "mull %4 \n\t"
00287 "addl %%ecx, %%eax \n\t"
00288 "adcl $0, %%edx \n\t"
00289 "movl $1000000000, %%ecx \n\t"
00290 "shld $5, %%eax, %%edx \n\t"
00291 "shll $5, %%eax \n\t"
00292 "divl %%ecx \n\t"
00293 : "=a" (*s), "=d" (*ns), "=&c" (dummy)
00294 : "A" (tsc), "g" (l4_scaler_tsc_to_ns)
00295 );
00296 }
00297
00298 L4_INLINE l4_cpu_time_t
00299 l4_ns_to_tsc (l4_uint64_t ns)
00300 {
00301     l4_uint32_t dummy;
00302     l4_cpu_time_t tsc;
00303     __asm__
00304 ("      \n\t"
00305 "movl %%edx, %%ecx \n\t"
00306 "mull %3 \n\t"
00307 "movl %%ecx, %%eax \n\t"
00308 "movl %%edx, %%ecx \n\t"
00309 "mull %3 \n\t"
00310 "addl %%ecx, %%eax \n\t"
00311 "adcl $0, %%edx \n\t"
00312 "shld $5, %%eax, %%edx \n\t"
00313 "shll $5, %%eax \n\t"
00314 : "=A" (tsc),
00315 "=&c" (dummy)
00316 : "0" (ns),
00317 "g" (l4_scaler_ns_to_tsc)
00318 );
00319 return tsc;
00320 }
00321
00322 L4_INLINE void

```


```
00323 l4_busy_wait_ns (l4_uint64_t ns)
00324 {
00325     l4_cpu_time_t stop = l4_rdtsc();
00326     stop += l4_ns_to_tsc(ns);
00327
00328     while (l4_rdtsc() < stop)
00329         ;
00330 }
00331
00332 L4_INLINE void
00333 l4_busy_wait_us (l4_uint64_t us)
00334 {
00335     l4_cpu_time_t stop = l4_rdtsc ();
00336     stop += l4_ns_to_tsc(us*1000ULL);
00337
00338     while (l4_rdtsc() < stop)
00339         ;
00340 }
00341
00342 #endif /* __l4_rdtsc_h */
00343
```

## 16.86 amd64/l4/util/spin.h File Reference

Spinning for amd64.

```
#include <l4/sys/compiler.h>
```

Include dependency graph for spin.h:



### 16.86.1 Detailed Description

Spinning for amd64.

Definition in file [spin.h](#).

## 16.87 spin.h

[Go to the documentation of this file.](#)

```

00001
00005 /*
00006  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00007  * Torsten Frenzel <frenzel@os.inf.tu-dresden.de>
00008  * economic rights: Technische Universität Dresden (Germany)
00009  * License: see LICENSE.spdx (in this directory or the directories above)
00010  */
00011 #ifndef __l4util_spin_h
00012 #define __l4util_spin_h
00013
00014 #include <l4/sys/compiler.h>
00015
00016 L4_BEGIN_DECLS
00017
00018 L4_CV void l4_spin(int x,int y);
00019 L4_CV void l4_spin_vga(int x,int y);
00020 L4_CV void l4_spin_n_text(int x, int y, int len, const char*s);
00021 L4_CV void l4_spin_n_text_vga(int x, int y, int len, const char*s);
00022
00023 /*****
00024  *
00025  * spin_text() - spinning wheel at the hercules screen. The given text
00026  * must be a text constant, no variables or arrays. Its
00027  * size is determined with the sizeof operator, it's much
00028  * faster than the strlen function.
00029  * spin_text_vga() - same for vga.
00030  *
00031  *****/
00032 #define l4_spin_text(x, y, text) \
00033     l4_spin_n_text((x), (y), sizeof(text)-1, "" text)
00034 #define l4_spin_text_vga(x, y, text) \
00035     l4_spin_n_text_vga((x), (y), sizeof(text)-1, "" text)
00036
00037 L4_END_DECLS
00038
00039 #endif


```

## 16.88 x86/l4/util/spin.h File Reference

Spinning for x86.

```
#include <l4/sys/compiler.h>
```

Include dependency graph for spin.h:



## 16.88.1 Detailed Description

Spinning for x86.

Definition in file [spin.h](#).

## 16.89 spin.h

[Go to the documentation of this file.](#)

```

00001
00005 /*
00006  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00007  *      Frank Mehnert <fm3@os.inf.tu-dresden.de>
00008  *      economic rights: Technische Universität Dresden (Germany)
00009  * License: see LICENSE.spdx (in this directory or the directories above)
00010  */
00011 #ifndef __l4util_spin_h
00012 #define __l4util_spin_h
00013
00014 #include <l4/sys/compiler.h>
00015
00016 L4_BEGIN_DECLS
00017
00018 L4_CV void l4_spin(int x,int y);
00019 L4_CV void l4_spin_vga(int x,int y);
00020 L4_CV void l4_spin_n_text(int x, int y, int len, const char*s);
00021 L4_CV void l4_spin_n_text_vga(int x, int y, int len, const char*s);
00022
00023 /*****
00024  *
00025  * spin_text()      - spinning wheel at the hercules screen. The given text
00026  *                   must be a text constant, no variables or arrays. Its
00027  *                   size is determined with the sizeof operator, it's much
00028  *                   faster than the strlen function.
00029  * spin_text_vga() - same for vga.
00030  *
00031  *****/
00032 #define l4_spin_text(x, y, text) \
00033     l4_spin_n_text((x), (y), sizeof(text)-1, "" text)
00034 #define l4_spin_text_vga(x, y, text) \
00035     l4_spin_n_text_vga((x), (y), sizeof(text)-1, "" text)
00036
00037 L4_END_DECLS
00038
00039 #endif

```

## 16.90 \_\_kip-arch.h

```

00001 /*
00002  * (c) 2013 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00003  *      economic rights: Technische Universität Dresden (Germany)
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007 #pragma once
00008
00009 struct l4_kip_platform_info_arch
00010 {};

```

## 16.91 \_\_kip-arch.h

```

00001 /*
00002  * (c) 2013 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00003  *      economic rights: Technische Universität Dresden (Germany)
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007 #pragma once
00008

```

```

00014 struct l4_kip_platform_info_arch
00015 {
00016     struct
00017     {
00018         l4_uint32_t MIDR, CTR, TCMTR, TLBTR, MPIDR, REVIDR;
00019         l4_uint32_t ID_PFR[2], ID_DFR0, ID_AFR0, ID_MMFR[4], ID_ISAR[6];
00020     } cpuinfo;
00021 };

```

## 16.92 \_\_kip-arch.h

```

00001 /*
00002  * (c) 2013 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00003  *     economic rights: Technische Universität Dresden (Germany)
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007 #pragma once
00008
00014 struct l4_kip_platform_info_arch
00015 {
00016     struct
00017     {
00018         l4_uint64_t MIDR, MPIDR, REVIDR;
00019         l4_uint64_t ID_PFR[3], ID_DFR0, ID_AFR0, ID_MMFR[4], ID_ISAR[7], ID_MVFR[3];
00020         l4_uint64_t ID_AA64DFR[2], ID_AA64ISAR[3], ID_AA64MMFR[3], ID_AA64PFR[2];
00021     } cpuinfo;
00022 };

```

## 16.93 \_\_kip-arch.h

```

00001 /*
00002  * (c) 2013 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00003  *     economic rights: Technische Universität Dresden (Germany)
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007 #pragma once
00008
00009 struct l4_kip_platform_info_arch
00010 {};


```

## 16.94 amd64/l4/sys/\_\_vcpu-arch.h File Reference

AMD64-specific vCPU interface.

```
#include <l4/sys/types.h>
```

Include dependency graph for \_\_vcpu-arch.h:



## Data Structures

- struct [l4\\_vcpu\\_arch\\_state\\_t](#)  
*Architecture-specific vCPU state.*
- struct [l4\\_vcpu\\_regs\\_t](#)  
*vCPU registers.*
- struct [l4\\_vcpu\\_ipc\\_regs\\_t](#)  
*vCPU message registers.*

## Typedefs

- typedef struct `l4_vcpu_arch_state_t` [l4\\_vcpu\\_arch\\_state\\_t](#)  
*Architecture-specific vCPU state.*
- typedef struct `l4_vcpu_regs_t` [l4\\_vcpu\\_regs\\_t](#)  
*vCPU registers.*
- typedef struct `l4_vcpu_ipc_regs_t` [l4\\_vcpu\\_ipc\\_regs\\_t](#)  
*vCPU message registers.*

## Enumerations

- enum { [L4\\_VCPU\\_STATE\\_VERSION](#) = 0x26 , [L4\\_VCPU\\_STATE\\_SIZE](#) = 0x200 , [L4\\_VCPU\\_STATE\\_EXT\\_SIZE](#) = [L4\\_PAGESIZE](#) }
  - enum [l4\\_vcpu\\_state\\_offset](#) { [L4\\_VCPU\\_OFFSET\\_EXT\\_STATE](#) = 0x400 , [L4\\_VCPU\\_OFFSET\\_EXT\\_INFOS](#) = 0x200 }
- Offsets for vCPU state layouts.*

### 16.94.1 Detailed Description

AMD64-specific vCPU interface.

Definition in file [\\_\\_vcpu-arch.h](#).

### 16.94.2 Enumeration Type Documentation

#### 16.94.2.1 anonymous enum

anonymous enum

#### Enumerator

L4_VCPU_STATE_VERSION	Architecture-specific version ID. This ID must match the version field in the <a href="#">l4_vcpu_state_t</a> structure after enabling vCPU mode or extended vCPU mode for a thread.
-----------------------	--

Definition at line 16 of file [\\_\\_vcpu-arch.h](#).

## 16.95 \_\_vcpu-arch.h

[Go to the documentation of this file.](#)

```

00001 /*
00002  * (c) 2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00003  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00004  *      economic rights: Technische Universität Dresden (Germany)
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00012 #pragma once
00013
00014 #include <l4/sys/types.h>
00015
00016 enum
00017 {
00024     L4_VCPU_STATE_VERSION = 0x26,
00025
00026     L4_VCPU_STATE_SIZE = 0x200,
00027     L4_VCPU_STATE_EXT_SIZE = L4_PAGESIZE,
00028 };
00029
00034 enum L4_vcpu_state_offset
00035 {
00036     L4_VCPU_OFFSET_EXT_STATE = 0x400,
00037     L4_VCPU_OFFSET_EXT_INFOS = 0x200,
00038 };
00039
00043 typedef struct l4_vcpu_arch_state_t
00044 {
00045     l4_umword_t host_fs_base;
00046     l4_umword_t host_gs_base;
00047     l4_uint16_t host_ds, host_es, host_fs, host_gs;
00048
00049     l4_uint16_t const user_ds32;
00050     l4_uint16_t const user_cs64;
00051     l4_uint16_t const user_cs32;
00052 } l4_vcpu_arch_state_t;
00053
00054
00059 typedef struct l4_vcpu_regs_t
00060 {
00061     l4_umword_t r15;
00062     l4_umword_t r14;
00063     l4_umword_t r13;

```



```

00064  l4_umword_t  r12;
00065  l4_umword_t  r11;
00066  l4_umword_t  r10;
00067  l4_umword_t  r9;
00068  l4_umword_t  r8;
00069
00070  l4_umword_t  di;
00071  l4_umword_t  si;
00072  l4_umword_t  bp;
00073  l4_umword_t  pfa;
00074  l4_umword_t  bx;
00075  l4_umword_t  dx;
00076  l4_umword_t  cx;
00077  l4_umword_t  ax;
00078
00079  l4_umword_t  trapno;
00080  l4_umword_t  err;
00081
00082  l4_umword_t  ip;
00083  l4_umword_t  cs;
00084  l4_umword_t  flags;
00085  l4_umword_t  sp;
00086  l4_umword_t  ss;
00087  l4_umword_t  fs_base;
00088  l4_umword_t  gs_base;
00089  l4_uint16_t  ds, es, fs, gs;
00090
00091 } l4_vcpu_regs_t;
00092
00097 typedef struct l4_vcpu_ipc_regs_t
00098 {
00099     l4_umword_t  _res[1];
00100     l4_umword_t  label;
00101     l4_umword_t  _res2[5];
00102     l4_msgtag_t  tag;
00103 } l4_vcpu_ipc_regs_t;

```

## 16.96 arm/l4/sys/\_\_vcpu-arch.h File Reference


ARM-specific vCPU interface.

```

#include <l4/sys/types.h>
#include <l4/sys/__vcpu-arm.h>

```

Include dependency graph for \_\_vcpu-arch.h:



## Data Structures

- struct [l4\\_vcpu\\_regs\\_t](#)  
*vCPU registers.*
- struct [l4\\_vcpu\\_arch\\_state\\_t](#)  
*Architecture-specific vCPU state.*
- struct [l4\\_vcpu\\_ipc\\_regs\\_t](#)  
*vCPU message registers.*

## Typedefs

- typedef struct [l4\\_vcpu\\_regs\\_t](#) **[l4\\_vcpu\\_regs\\_t](#)**  
*vCPU registers.*
- typedef struct [l4\\_vcpu\\_arch\\_state\\_t](#) **[l4\\_vcpu\\_arch\\_state\\_t](#)**  
*Architecture-specific vCPU state.*
- typedef struct [l4\\_vcpu\\_ipc\\_regs\\_t](#) **[l4\\_vcpu\\_ipc\\_regs\\_t](#)**  
*vCPU message registers.*

## Enumerations

- enum { [L4\\_VCPU\\_STATE\\_VERSION](#) = 0x38 , [L4\\_VCPU\\_STATE\\_SIZE](#) = 0x100 , [L4\\_VCPU\\_STATE\\_EXT\\_SIZE](#) = 0x400 }
  - enum [L4\\_vcpu\\_state\\_offset](#) { [L4\\_VCPU\\_OFFSET\\_EXT\\_STATE](#) = 0x180 , [L4\\_VCPU\\_OFFSET\\_EXT\\_INFOS](#) = 0x100 }
  - enum [L4\\_vcpu\\_e\\_field\\_ids](#) { }
- Offsets for vCPU state layouts.*
- IDs for extended vCPU state fields.*

## 16.96.1 Detailed Description

ARM-specific vCPU interface.

Definition in file [\\_\\_vcpu-arch.h](#).

## 16.96.2 Enumeration Type Documentation

### 16.96.2.1 anonymous enum

anonymous enum

## Enumerator

<a href="#">L4_VCPU_STATE_VERSION</a>	Architecture-specific version ID. This ID must match the version field in the <a href="#">l4_vcpu_state_t</a> structure after enabling vCPU mode or extended vCPU mode for a thread.
---------------------------------------	--

Definition at line 17 of file [\\_\\_vcpu-arch.h](#).

### 16.96.2.2 L4\_vcpu\_e\_field\_ids

enum [L4\\_vcpu\\_e\\_field\\_ids](#)

IDs for extended vCPU state fields.

Bits 14..15: are the field size:

- 0 = 32bit field
- 1 = register width field
- 2 = 64bit field

#### Enumerator

L4_VCPU_E_VTMR_CFG	vtimer irq configuration
--------------------	--------------------------

Definition at line 99 of file [\\_\\_vcpu-arch.h](#).

## 16.97 \_\_vcpu-arch.h

[Go to the documentation of this file.](#)

```

00001 /*
00002  * (c) 2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00003  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00004  *      economic rights: Technische Universität Dresden (Germany)
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00012 #pragma once
00013
00014 #include <l4/sys/types.h>
00015 #include <l4/sys/__vcpu-arm.h>
00016
00017 enum
00018 {
00025     L4_VCPU_STATE_VERSION = 0x38,
00026
00027     L4_VCPU_STATE_SIZE = 0x100,
00028     L4_VCPU_STATE_EXT_SIZE = 0x400,
00029 };
00030
00035 enum L4_vcpu_state_offset
00036 {
00037     L4_VCPU_OFFSET_EXT_STATE = 0x180,
00038     L4_VCPU_OFFSET_EXT_INFOS = 0x100,
00039 };
00040
00041 L4_INLINE l4_arm_vcpu_e_info_t const *
00042 l4_vcpu_e_info(void const *vcpu) L4_NOTHROW
00043 {
00044     return (l4_arm_vcpu_e_info_t const *) ((l4_addr_t)vcpu
00045                                             + L4_VCPU_OFFSET_EXT_INFOS);
00046 }
00047
00048 L4_INLINE void *l4_vcpu_e_ptr(void const *vcpu, unsigned id) L4_NOTHROW
00049 { return (void *) ((l4_addr_t)vcpu + L4_VCPU_OFFSET_EXT_STATE + (id & 0xfff)); }
00050
00055 typedef struct l4_vcpu_regs_t
00056 {
00057     l4_umword_t pfa;
00058     l4_umword_t err;
00059
00060     l4_umword_t r[13];
00061
00062     l4_umword_t sp;
00063     l4_umword_t lr;

```

```

00064     l4_umword_t _dummy;
00065     l4_umword_t ip;
00066     l4_umword_t flags;
00067     l4_umword_t tpidruro;
00068     l4_umword_t tpidrurw;
00069 } l4_vcpu_regs_t;
00070
00074 typedef struct l4_vcpu_arch_state_t
00075 {
00076     l4_umword_t host_tpidruro;
00077 } l4_vcpu_arch_state_t;
00078
00083 typedef struct l4_vcpu_ipc_regs_t
00084 {
00085     l4_msgtag_t tag;
00086     l4_umword_t _d1[3];
00087     l4_umword_t label;
00088     l4_umword_t _d2[8];
00089 } l4_vcpu_ipc_regs_t;
00090
00099 enum L4_vcpu_e_field_ids
00100 {
00101     L4_VCPU_E_HCR           = 0x8008,
00102     L4_VCPU_E_TTBRO        = 0x8010,
00103     L4_VCPU_E_TTBRI        = 0x8018,
00104     L4_VCPU_E_TTBRI        = 0x0020,
00105     L4_VCPU_E_SCTLR        = 0x0024,
00106     L4_VCPU_E_DACR         = 0x0028,
00107     L4_VCPU_E_FCSEIDR      = 0x002c,
00108
00109     L4_VCPU_E_CNTVCTL       = 0x0030,
00110     L4_VCPU_E_CNTVOFF      = 0x8038,
00111
00112     L4_VCPU_E_VMPIDR        = 0x0040,
00113     L4_VCPU_E_VPIDR         = 0x0044,
00114
00115     L4_VCPU_E_VTMR_CFG      = 0x0048,
00116
00117     L4_VCPU_E_GIC_HCR       = 0x0050,
00118     L4_VCPU_E_GIC_VTR       = 0x0054,
00119     L4_VCPU_E_GIC_VMCR      = 0x0058,
00120     L4_VCPU_E_GIC_MISR      = 0x005c,
00121     L4_VCPU_E_GIC_EISR      = 0x0060,
00122     L4_VCPU_E_GIC_ELSR      = 0x0064,
00123     L4_VCPU_E_GIC_V2_LR0    = 0x0068,
00124     L4_VCPU_E_GIC_V3_LR0    = 0x8068,
00125 };

```

## 16.98 arm64/l4/sys/\_\_vcpu-arch.h File Reference


ARM64-specific vCPU interface.

```

#include <l4/sys/types.h>
#include <l4/sys/utcb.h>
#include <l4/sys/__vcpu-arm.h>

```

Include dependency graph for \_\_vcpu-arch.h:



## Data Structures

- struct [l4\\_vcpu\\_arch\\_state\\_t](#)  
*Architecture-specific vCPU state.*
- struct [l4\\_vcpu\\_ipc\\_regs\\_t](#)  
*vCPU message registers.*

## Typedefs

- typedef [l4\\_exc\\_regs\\_t](#) [l4\\_vcpu\\_regs\\_t](#)  
*vCPU registers.*
- typedef struct [l4\\_vcpu\\_arch\\_state\\_t](#) [l4\\_vcpu\\_arch\\_state\\_t](#)  
*Architecture-specific vCPU state.*
- typedef struct [l4\\_vcpu\\_ipc\\_regs\\_t](#) [l4\\_vcpu\\_ipc\\_regs\\_t](#)  
*vCPU message registers.*

## Enumerations

- enum { [L4\\_VCPU\\_STATE\\_VERSION](#) = 0x38 , [L4\\_VCPU\\_STATE\\_SIZE](#) = 0x200 , [L4\\_VCPU\\_STATE\\_EXT\\_SIZE](#) = 0x800 }
  - enum [l4\\_vcpu\\_state\\_offset](#) { [L4\\_VCPU\\_OFFSET\\_EXT\\_STATE](#) = 0x280 , [L4\\_VCPU\\_OFFSET\\_EXT\\_INFOS](#) = 0x200 }
  - enum [l4\\_vcpu\\_e\\_field\\_ids](#) { }
- Offsets for vCPU state layouts.*
- IDs for extended vCPU state fields.*

## 16.98.1 Detailed Description

ARM64-specific vCPU interface.

Definition in file [\\_\\_vcpu-arch.h](#).

## 16.98.2 Enumeration Type Documentation

### 16.98.2.1 anonymous enum

anonymous enum

#### Enumerator

L4_VCPU_STATE_VERSION	Architecture-specific version ID. This ID must match the version field in the <a href="#">l4_vcpu_state_t</a> structure after enabling vCPU mode or extended vCPU mode for a thread.
-----------------------	--

Definition at line 18 of file [\\_\\_vcpu-arch.h](#).

### 16.98.2.2 L4\_vcpu\_e\_field\_ids

enum [L4\\_vcpu\\_e\\_field\\_ids](#)

IDs for extended vCPU state fields.

Bits 14..15: are the field size:

- 0 = 32bit field
- 1 = register width field
- 2 = 64bit field

#### Enumerator

L4_VCPU_E_VTMR_CFG	vtimer irq configuration
--------------------	--------------------------

Definition at line 85 of file [\\_\\_vcpu-arch.h](#).

## 16.99 \_\_vcpu-arch.h

[Go to the documentation of this file.](#)

```

00001 /*
00002  * (c) 2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00003  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00004  *      economic rights: Technische Universität Dresden (Germany)
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00012 #pragma once
00013
00014 #include <l4/sys/types.h>
00015 #include <l4/sys/utcb.h>
00016 #include <l4/sys/__vcpu-arm.h>
00017
00018 enum
00019 {
00026   L4_VCPU_STATE_VERSION = 0x38,
00027
00028   L4_VCPU_STATE_SIZE = 0x200,

```

```

00029  L4_VCPU_STATE_EXT_SIZE = 0x800,
00030  };
00031
00036  enum L4_vcpu_state_offset
00037  {
00038      L4_VCPU_OFFSET_EXT_STATE = 0x280,
00039      L4_VCPU_OFFSET_EXT_INFOS = 0x200,
00040  };
00041
00042  L4_INLINE l4_arm_vcpu_e_info_t const *
00043  l4_vcpu_e_info(void const *vcpu) L4_NOTHROW
00044  {
00045      return (l4_arm_vcpu_e_info_t const *)((l4_addr_t)vcpu
00046                                              + L4_VCPU_OFFSET_EXT_INFOS);
00047  }
00048
00049  L4_INLINE void *l4_vcpu_e_ptr(void const *vcpu, unsigned id) L4_NOTHROW
00050  { return (void *)((l4_addr_t)vcpu + L4_VCPU_OFFSET_EXT_STATE + (id & 0xfff)); }
00051
00056  typedef l4_exc_regs_t l4_vcpu_regs_t;
00057
00061  typedef struct l4_vcpu_arch_state_t
00062  {
00063      l4_umword_t host_tpidrulo;
00064  } l4_vcpu_arch_state_t;
00065
00070  typedef struct l4_vcpu_ipc_regs_t
00071  {
00072      l4_msgtag_t tag;
00073      l4_umword_t label;
00074      l4_umword_t _d1[3];
00075  } l4_vcpu_ipc_regs_t;
00076
00085  enum L4_vcpu_e_field_ids
00086  {
00087      L4_VCPU_E_HCR          = 0x8008,
00088      L4_VCPU_E_SCTLR        = 0x0010,
00089      L4_VCPU_E_CPACR        = 0x0014,
00090
00091      L4_VCPU_E_CNTVCTL       = 0x0018,
00092      L4_VCPU_E_CNTVOFF       = 0x8020,
00093
00094      L4_VCPU_E_VMPIDR        = 0x8028,
00095      L4_VCPU_E_VPIDR         = 0x0030,
00096
00097      L4_VCPU_E_VTMR_CFG      = 0x0034,
00098      L4_VCPU_E_VTCR          = 0x8038,
00099
00100      L4_VCPU_E_GIC_HCR       = 0x0040,
00101      L4_VCPU_E_GIC_VTR       = 0x0044,
00102      L4_VCPU_E_GIC_VMCR      = 0x0048,
00103      L4_VCPU_E_GIC_MISR      = 0x004c,
00104      L4_VCPU_E_GIC_EISR      = 0x0050,
00105      L4_VCPU_E_GIC_ELSR      = 0x0054,
00106      L4_VCPU_E_GIC_V2_LR0     = 0x0058,
00107      L4_VCPU_E_GIC_V3_LR0     = 0x8058,
00108  };


```

## 16.100 x86/I4/sys/\_\_\_vcpu-arch.h File Reference

x86-specific vCPU interface.

```
#include <l4/sys/types.h>
```

Include dependency graph for `__vcpu-arch.h`:



## Data Structures

- struct [l4\\_vcpu\\_regs\\_t](#)  
*vCPU registers.*
- struct [l4\\_vcpu\\_arch\\_state\\_t](#)  
*Architecture-specific vCPU state.*
- struct [l4\\_vcpu\\_ipc\\_regs\\_t](#)  
*vCPU message registers.*

## Typedefs

- typedef struct `l4_vcpu_regs_t` **`l4_vcpu_regs_t`**  
*vCPU registers.*
- typedef struct `l4_vcpu_arch_state_t` **`l4_vcpu_arch_state_t`**  
*Architecture-specific vCPU state.*
- typedef struct `l4_vcpu_ipc_regs_t` **`l4_vcpu_ipc_regs_t`**  
*vCPU message registers.*

## Enumerations

- enum { [L4\\_VCPU\\_STATE\\_VERSION](#) = 0x46 , [L4\\_VCPU\\_STATE\\_SIZE](#) = 0x200 , [L4\\_VCPU\\_STATE\\_EXT](#) ↔ [\\_SIZE](#) = [L4\\_PAGESIZE](#) }
  - enum [L4\\_vcpu\\_state\\_offset](#) { [L4\\_VCPU\\_OFFSET\\_EXT\\_STATE](#) = 0x400 , [L4\\_VCPU\\_OFFSET\\_EXT\\_INFOS](#) = 0x200 }
- Offsets for vCPU state layouts.*



## 16.100.1 Detailed Description

x86-specific vCPU interface.

Definition in file [\\_\\_vcpu-arch.h](#).

## 16.100.2 Enumeration Type Documentation

### 16.100.2.1 anonymous enum

anonymous enum

#### Enumerator

L4_VCPU_STATE_VERSION	Architecture-specific version ID. This ID must match the version field in the <a href="#">l4_vcpu_state_t</a> structure after enabling vCPU mode or extended vCPU mode for a thread.
-----------------------	--

Definition at line 16 of file [\\_\\_vcpu-arch.h](#).

## 16.101 \_\_vcpu-arch.h

[Go to the documentation of this file.](#)

```

00001 /*
00002  * (c) 2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00003  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00004  *      economic rights: Technische Universität Dresden (Germany)
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00012 #pragma once
00013
00014 #include <l4/sys/types.h>
00015
00016 enum
00017 {
00024     L4_VCPU_STATE_VERSION = 0x46,
00025
00026     L4_VCPU_STATE_SIZE = 0x200,
00027     L4_VCPU_STATE_EXT_SIZE = L4_PAGESIZE,
00028 };
00029
00034 enum L4_vcpu_state_offset
00035 {
00036     L4_VCPU_OFFSET_EXT_STATE = 0x400,
00037     L4_VCPU_OFFSET_EXT_INFOS = 0x200,
00038 };
00039
00044 typedef struct l4_vcpu_regs_t
00045 {
00046     l4_umword_t es;
00047     l4_umword_t ds;
00048     l4_umword_t gs;
00049     l4_umword_t fs;
00050
00051     l4_umword_t di;
00052     l4_umword_t si;
00053     l4_umword_t bp;
00054     l4_umword_t pfa;
00055     l4_umword_t bx;
00056     l4_umword_t dx;
00057     l4_umword_t cx;
00058     l4_umword_t ax;
00059
00060     l4_umword_t trapno;

```

```

00061     l4_umword_t err;
00062
00063     l4_umword_t ip;
00064     l4_umword_t dummy1;
00065     l4_umword_t flags;
00066     l4_umword_t sp;
00067     l4_umword_t ss;
00068 } l4_vcpu_regs_t;
00069
00073 typedef struct l4_vcpu_arch_state_t { } l4_vcpu_arch_state_t;
00074
00079 typedef struct l4_vcpu_ipc_regs_t
00080 {
00081     l4_umword_t _res[2];
00082     l4_umword_t label;
00083     l4_umword_t _res2[3];
00084     l4_msgtag_t tag;
00085 } l4_vcpu_ipc_regs_t;

```

## 16.102 ktrace\_events.h

```

00001 /* Note, automatically generated from Fiasco binary */
00002 #pragma once
00003
00004 enum L4_ktrace_tbuf_entry_fixed
00005 {
00006     l4_ktrace_tbuf_unused = 0,
00007     l4_ktrace_tbuf_pf = 1,
00008     l4_ktrace_tbuf_ipc = 2,
00009     l4_ktrace_tbuf_ipc_res = 3,
00010     l4_ktrace_tbuf_ipc_trace = 4,
00011     l4_ktrace_tbuf_ke = 5,
00012     l4_ktrace_tbuf_ke_reg = 6,
00013     l4_ktrace_tbuf_breakpoint = 7,
00014     l4_ktrace_tbuf_ke_bin = 8,
00015     l4_ktrace_tbuf_dynentries = 9,
00016     l4_ktrace_tbuf_max = 128,
00017     l4_ktrace_tbuf_hidden = 128,
00018 };
00019
00020 typedef unsigned long L4_ktrace_t__Address;
00021 typedef unsigned long L4_ktrace_t__Cap_index;
00022 typedef void L4_ktrace_t__Context;
00023 typedef void L4_ktrace_t__Context__Drq;
00024 typedef unsigned L4_ktrace_t__Context__Drq_log__Type;
00025 typedef unsigned L4_ktrace_t__Cpu_number;
00026 typedef void L4_ktrace_t__Irq_base;
00027 typedef void L4_ktrace_t__Irq_chip;
00028 typedef void L4_ktrace_t__Kobject;
00029 typedef unsigned long L4_ktrace_t__L4_error;
00030 typedef unsigned long L4_ktrace_t__L4_msg_tag;
00031 typedef unsigned long L4_ktrace_t__L4_obj_ref;
00032 typedef unsigned L4_ktrace_t__L4_timeout_pair;
00033 typedef unsigned long L4_ktrace_t__Mword;
00034 typedef void L4_ktrace_t__Rcu_item;
00035 typedef void L4_ktrace_t__Sched_context;
00036 typedef long L4_ktrace_t__Smword;
00037 typedef void L4_ktrace_t__Space;
00038 typedef unsigned short L4_ktrace_t__Unsigned16;
00039 typedef unsigned int L4_ktrace_t__Unsigned32;
00040 typedef unsigned long long L4_ktrace_t__Unsigned64;
00041 typedef unsigned char L4_ktrace_t__Unsigned8;
00042 typedef void L4_ktrace_t__cxx__Type_info;
00043
00044 typedef struct __attribute__((packed))
00045 {
00046     L4_ktrace_t__Mword _number; /* 0+8 */
00047     L4_ktrace_t__Address _ip; /* 8+8 */
00048     L4_ktrace_t__Unsigned64 _tsc; /* 16+8 */
00049     L4_ktrace_t__Context *_ctx; /* 24+8 */
00050     L4_ktrace_t__Unsigned32 _pmc1; /* 32+4 */
00051     L4_ktrace_t__Unsigned32 _pmc2; /* 36+4 */
00052     L4_ktrace_t__Unsigned32 _kclock; /* 40+4 */
00053     L4_ktrace_t__Unsigned8 _type; /* 44+1 */
00054     L4_ktrace_t__Unsigned8 _cpu; /* 45+1 */
00055     union __attribute__((packed))
00056     {
00057         struct __attribute__((packed))
00058         {
00059             char __pre_pad[2];
00060             void *func; /* 48+8 */
00061             L4_ktrace_t__Context *thread; /* 56+8 */
00062             L4_ktrace_t__Context__Drq *rq; /* 64+8 */

```

```

00063     L4_ktrace_t__Cpu_number target_cpu; /* 72+4 */
00064     L4_ktrace_t__Context__Drq_log__Type type; /* 76+4 */
00065     char wait; /* 80+1 */
00066 } drq; /* 88 */
00067 struct __attribute__((__packed__))
00068 {
00069     char __pre_pad[2];
00070     L4_ktrace_t__Mword state; /* 48+8 */
00071     L4_ktrace_t__Mword ip; /* 56+8 */
00072     L4_ktrace_t__Mword sp; /* 64+8 */
00073     L4_ktrace_t__Mword space; /* 72+8 */
00074     L4_ktrace_t__Mword err; /* 80+8 */
00075     unsigned char type; /* 88+1 */
00076     unsigned char trap; /* 89+1 */
00077 } vcpu; /* 96 */
00078 struct __attribute__((__packed__))
00079 {
00080     char __pre_pad[2];
00081     L4_ktrace_t__Sword op; /* 48+8 */
00082     L4_ktrace_t__Cap_index buffer; /* 56+8 */
00083     L4_ktrace_t__Mword id; /* 64+8 */
00084     L4_ktrace_t__Mword ram; /* 72+8 */
00085     L4_ktrace_t__Mword newo; /* 80+8 */
00086 } factory; /* 88 */
00087 struct __attribute__((__packed__))
00088 {
00089     char __pre_pad[2];
00090     L4_ktrace_t__Mword gate_dbg_id; /* 48+8 */
00091     L4_ktrace_t__Mword thread_dbg_id; /* 56+8 */
00092     L4_ktrace_t__Mword label; /* 64+8 */
00093 } gate; /* 72 */
00094 struct __attribute__((__packed__))
00095 {
00096     char __pre_pad[2];
00097     L4_ktrace_t__Irq_base *obj; /* 48+8 */
00098     L4_ktrace_t__Irq_chip *chip; /* 56+8 */
00099     L4_ktrace_t__Mword pin; /* 64+8 */
00100 } irq; /* 72 */
00101 struct __attribute__((__packed__))
00102 {
00103     char __pre_pad[2];
00104     L4_ktrace_t__Kobject *obj; /* 48+8 */
00105     L4_ktrace_t__Mword id; /* 56+8 */
00106     L4_ktrace_t__cxx__Type_info *type; /* 64+8 */
00107     L4_ktrace_t__Mword ram; /* 72+8 */
00108 } destroy; /* 80 */
00109 struct __attribute__((__packed__))
00110 {
00111     char __pre_pad[2];
00112     L4_ktrace_t__Cpu_number cpu; /* 48+4 */
00113     char __pad_l[4];
00114     L4_ktrace_t__Rcu_item *item; /* 56+8 */
00115     void *cb; /* 64+8 */
00116     unsigned char event; /* 72+1 */
00117 } rcu; /* 80 */
00118 struct __attribute__((__packed__))
00119 {
00120     char __pre_pad[2];
00121     L4_ktrace_t__Mword id; /* 48+8 */
00122     L4_ktrace_t__Mword mask; /* 56+8 */
00123     L4_ktrace_t__Mword fpage; /* 64+8 */
00124     char map; /* 72+1 */
00125 } tmap; /* 80 */
00126 struct __attribute__((__packed__))
00127 {
00128     char __pre_pad[2];
00129     L4_ktrace_t__Address _address; /* 48+8 */
00130     int _len; /* 56+4 */
00131     char __pad_l[4];
00132     L4_ktrace_t__Mword _value; /* 64+8 */
00133     int _mode; /* 72+4 */
00134 } bp; /* 80 */
00135 struct __attribute__((__packed__))
00136 {
00137     char __pre_pad[2];
00138     L4_ktrace_t__Context *dst; /* 48+8 */
00139     L4_ktrace_t__Context *dst_orig; /* 56+8 */
00140     L4_ktrace_t__Address kernel_ip; /* 64+8 */
00141     L4_ktrace_t__Mword lock_cnt; /* 72+8 */
00142     L4_ktrace_t__Space *from_space; /* 80+8 */
00143     L4_ktrace_t__Sched_context *from_sched; /* 88+8 */
00144     L4_ktrace_t__Mword from_prio; /* 96+8 */
00145 } context_switch; /* 104 */
00146 struct __attribute__((__packed__))
00147 {
00148     } empty; /* 48 */
00149 struct __attribute__((__packed__))

```

```

00150     {
00151         char __pre_pad[2];
00152         L4_ktrace_t__L4_msg_tag_tag; /* 48+8 */
00153         L4_ktrace_t__Mword_dword[2]; /* 56+16 */
00154         L4_ktrace_t__L4_obj_ref_dst; /* 72+8 */
00155         L4_ktrace_t__Mword_dbg_id; /* 80+8 */
00156         L4_ktrace_t__Mword_label; /* 88+8 */
00157         L4_ktrace_t__L4_timeout_pair_timeout; /* 96+4 */
00158         char __pad_1[4];
00159         L4_ktrace_t__Unsigned64_to_abs_rcv; /* 104+8 */
00160     } ipc; /* 112 */
00161     struct __attribute__((__packed__))
00162     {
00163         L4_ktrace_t__Unsigned8_have_snd; /* 46+1 */
00164         L4_ktrace_t__Unsigned8_is_np; /* 47+1 */
00165         L4_ktrace_t__L4_msg_tag_tag; /* 48+8 */
00166         L4_ktrace_t__Mword_dword[2]; /* 56+16 */
00167         L4_ktrace_t__L4_error_result; /* 72+8 */
00168         L4_ktrace_t__Mword_from; /* 80+8 */
00169         L4_ktrace_t__L4_obj_ref_dst; /* 88+8 */
00170         L4_ktrace_t__Mword_pair_event; /* 96+8 */
00171     } ipc_res; /* 104 */
00172     struct __attribute__((__packed__))
00173     {
00174         char __pre_pad[2];
00175         union __attribute__((__packed__)) {
00176             char msg[80]; /* 0+80 */
00177             struct __attribute__((__packed__)) {
00178                 char tag[2]; /* 0+2 */
00179                 char __pad_1[6];
00180                 char *ptr; /* 8+8 */
00181             } mptr; /* 0+16 */
00182         } msg; /* 48+80 */
00183     } ke; /* 128 */
00184     struct __attribute__((__packed__))
00185     {
00186         char _msg[80]; /* 46+80 */
00187     } ke_bin; /* 128 */
00188     struct __attribute__((__packed__))
00189     {
00190         char __pre_pad[2];
00191         L4_ktrace_t__Mword v[3]; /* 48+24 */
00192         union __attribute__((__packed__)) {
00193             char msg[56]; /* 0+56 */
00194             struct __attribute__((__packed__)) {
00195                 char tag[2]; /* 0+2 */
00196                 char __pad_1[6];
00197                 char *ptr; /* 8+8 */
00198             } mptr; /* 0+16 */
00199         } msg; /* 72+56 */
00200     } ke_reg; /* 128 */
00201     struct __attribute__((__packed__))
00202     {
00203         char __pre_pad[2];
00204         L4_ktrace_t__Address_pfa; /* 48+8 */
00205         L4_ktrace_t__Mword_error; /* 56+8 */
00206         L4_ktrace_t__Space *space; /* 64+8 */
00207     } pf; /* 72 */
00208     struct __attribute__((__packed__))
00209     {
00210         unsigned short mode; /* 46+2 */
00211         L4_ktrace_t__Context *owner; /* 48+8 */
00212         unsigned short id; /* 56+2 */
00213         unsigned short prio; /* 58+2 */
00214         char __pad_1[4];
00215         long left; /* 64+8 */
00216         unsigned long quantum; /* 72+8 */
00217     } sched; /* 80 */
00218     struct __attribute__((__packed__))
00219     {
00220         char _trapno; /* 46+1 */
00221         char __pad_1[1];
00222         L4_ktrace_t__Unsigned16_error; /* 48+2 */
00223         char __pad_2[6];
00224         L4_ktrace_t__Mword_rbp; /* 56+8 */
00225         L4_ktrace_t__Mword_cr2; /* 64+8 */
00226         L4_ktrace_t__Mword_rax; /* 72+8 */
00227         L4_ktrace_t__Mword_rflags; /* 80+8 */
00228         L4_ktrace_t__Mword_rsp; /* 88+8 */
00229         L4_ktrace_t__Unsigned16_cs; /* 96+2 */
00230         L4_ktrace_t__Unsigned16_ds; /* 98+2 */
00231     } trap; /* 104 */
00232     struct __attribute__((__packed__))
00233     {
00234         char _padding[80]; /* 46+80 */
00235         char __post_pad[2]; /* 126+2 */
00236     } fullsize; /* 128 */

```

```

00237     struct __attribute__((__packed__))
00238     {
00239         char __pre_pad[2];
00240         L4_ktrace_t__Cap_index cap_idx; /* 48+8 */
00241     } ieh; /* 56 */
00242     struct __attribute__((__packed__))
00243     {
00244         char __pre_pad[2];
00245         L4_ktrace_t__Mword pfa; /* 48+8 */
00246         L4_ktrace_t__Cap_index cap_idx; /* 56+8 */
00247         L4_ktrace_t__Mword err; /* 64+8 */
00248     } ipfh; /* 72 */
00249     struct __attribute__((__packed__))
00250     {
00251         char __pre_pad[2];
00252         L4_ktrace_t__Mword id; /* 48+8 */
00253         L4_ktrace_t__Mword ip; /* 56+8 */
00254         L4_ktrace_t__Mword sp; /* 64+8 */
00255         L4_ktrace_t__Mword op; /* 72+8 */
00256     } exregs; /* 80 */
00257     struct __attribute__((__packed__))
00258     {
00259         char __pre_pad[2];
00260         L4_ktrace_t__Mword state; /* 48+8 */
00261         L4_ktrace_t__Address user_ip; /* 56+8 */
00262         L4_ktrace_t__Cpu_number src_cpu; /* 64+4 */
00263         L4_ktrace_t__Cpu_number target_cpu; /* 68+4 */
00264     } migration; /* 72 */
00265     struct __attribute__((__packed__))
00266     {
00267         char __pre_pad[2];
00268         L4_ktrace_t__Address user_ip; /* 48+8 */
00269     } timer; /* 56 */
00270     struct __attribute__((__packed__))
00271     {
00272         char __pre_pad[2];
00273         L4_ktrace_t__Mword exitcode; /* 48+8 */
00274         L4_ktrace_t__Mword exitinfo1; /* 56+8 */
00275         L4_ktrace_t__Mword exitinfo2; /* 64+8 */
00276         L4_ktrace_t__Mword rip; /* 72+8 */
00277     } svm; /* 80 */
00278     } m;
00279 } l4_tracebuffer_entry_t;

```

## 16.103 ktrace\_events.h

```

00001 /* Note, automatically generated from Fiasco binary */
00002 #pragma once
00003
00004 enum L4_ktrace_tbuf_entry_fixed
00005 {
00006     l4_ktrace_tbuf_unused = 0,
00007     l4_ktrace_tbuf_pf = 1,
00008     l4_ktrace_tbuf_ipc = 2,
00009     l4_ktrace_tbuf_ipc_res = 3,
00010     l4_ktrace_tbuf_ipc_trace = 4,
00011     l4_ktrace_tbuf_ke = 5,
00012     l4_ktrace_tbuf_ke_reg = 6,
00013     l4_ktrace_tbuf_breakpoint = 7,
00014     l4_ktrace_tbuf_ke_bin = 8,
00015     l4_ktrace_tbuf_dynentries = 9,
00016     l4_ktrace_tbuf_max = 128,
00017     l4_ktrace_tbuf_hidden = 128,
00018 };
00019
00020 typedef unsigned long L4_ktrace_t__Address;
00021 typedef unsigned long L4_ktrace_t__Cap_index;
00022 typedef void L4_ktrace_t__Context;
00023 typedef void L4_ktrace_t__Context__Drq;
00024 typedef unsigned L4_ktrace_t__Context__Drq_log__Type;
00025 typedef unsigned L4_ktrace_t__Cpu_number;
00026 typedef void L4_ktrace_t__Irq_base;
00027 typedef void L4_ktrace_t__Irq_chip;
00028 typedef void L4_ktrace_t__Kobject;
00029 typedef unsigned long L4_ktrace_t__L4_error;
00030 typedef unsigned long L4_ktrace_t__L4_msg_tag;
00031 typedef unsigned long L4_ktrace_t__L4_obj_ref;
00032 typedef unsigned L4_ktrace_t__L4_timeout_pair;
00033 typedef unsigned long L4_ktrace_t__Mword;
00034 typedef void L4_ktrace_t__Rcu_item;
00035 typedef void L4_ktrace_t__Sched_context;
00036 typedef long L4_ktrace_t__Sword;
00037 typedef void L4_ktrace_t__Space;

```

```

00038 typedef unsigned int L4_ktrace_t__Unsigned32;
00039 typedef unsigned long long L4_ktrace_t__Unsigned64;
00040 typedef unsigned char L4_ktrace_t__Unsigned8;
00041 typedef void L4_ktrace_t__cxx_Type_info;
00042
00043 typedef struct __attribute__((packed))
00044 {
00045     L4_ktrace_t__Mword _number; /* 0+4 */
00046     L4_ktrace_t__Address _ip; /* 4+4 */
00047     L4_ktrace_t__Unsigned64 _tsc; /* 8+8 */
00048     L4_ktrace_t__Context *_ctx; /* 16+4 */
00049     L4_ktrace_t__Unsigned32 _pmc1; /* 20+4 */
00050     L4_ktrace_t__Unsigned32 _pmc2; /* 24+4 */
00051     L4_ktrace_t__Unsigned32 _kclock; /* 28+4 */
00052     L4_ktrace_t__Unsigned8 _type; /* 32+1 */
00053     L4_ktrace_t__Unsigned8 _cpu; /* 33+1 */
00054     union __attribute__((__packed__))
00055     {
00056         struct __attribute__((__packed__))
00057         {
00058             char __pre_pad[2];
00059             void *func; /* 36+4 */
00060             L4_ktrace_t__Context *thread; /* 40+4 */
00061             L4_ktrace_t__Context__Drq *rq; /* 44+4 */
00062             L4_ktrace_t__Cpu_number target_cpu; /* 48+4 */
00063             L4_ktrace_t__Context__Drq_log__Type type; /* 52+4 */
00064             char wait; /* 56+1 */
00065         } drq; /* 64 */
00066         struct __attribute__((__packed__))
00067         {
00068             char __pre_pad[2];
00069             L4_ktrace_t__Mword state; /* 36+4 */
00070             L4_ktrace_t__Mword ip; /* 40+4 */
00071             L4_ktrace_t__Mword sp; /* 44+4 */
00072             L4_ktrace_t__Mword space; /* 48+4 */
00073             L4_ktrace_t__Mword err; /* 52+4 */
00074             unsigned char type; /* 56+1 */
00075             unsigned char trap; /* 57+1 */
00076         } vcpu; /* 64 */
00077         struct __attribute__((__packed__))
00078         {
00079             char __pre_pad[2];
00080             L4_ktrace_t__Smword op; /* 36+4 */
00081             L4_ktrace_t__Cap_index buffer; /* 40+4 */
00082             L4_ktrace_t__Mword id; /* 44+4 */
00083             L4_ktrace_t__Mword ram; /* 48+4 */
00084             L4_ktrace_t__Mword newo; /* 52+4 */
00085         } factory; /* 56 */
00086         struct __attribute__((__packed__))
00087         {
00088             char __pre_pad[2];
00089             L4_ktrace_t__Mword gate_dbg_id; /* 36+4 */
00090             L4_ktrace_t__Mword thread_dbg_id; /* 40+4 */
00091             L4_ktrace_t__Mword label; /* 44+4 */
00092         } gate; /* 48 */
00093         struct __attribute__((__packed__))
00094         {
00095             char __pre_pad[2];
00096             L4_ktrace_t__Irq_base *obj; /* 36+4 */
00097             L4_ktrace_t__Irq_chip *chip; /* 40+4 */
00098             L4_ktrace_t__Mword pin; /* 44+4 */
00099         } irq; /* 48 */
00100         struct __attribute__((__packed__))
00101         {
00102             char __pre_pad[2];
00103             L4_ktrace_t__Kobject *obj; /* 36+4 */
00104             L4_ktrace_t__Mword id; /* 40+4 */
00105             L4_ktrace_t__cxx_Type_info *type; /* 44+4 */
00106             L4_ktrace_t__Mword ram; /* 48+4 */
00107         } destroy; /* 56 */
00108         struct __attribute__((__packed__))
00109         {
00110             char __pre_pad[2];
00111             L4_ktrace_t__Cpu_number cpu; /* 36+4 */
00112             L4_ktrace_t__Rcu_item *item; /* 40+4 */
00113             void *cb; /* 44+4 */
00114             unsigned char event; /* 48+1 */
00115         } rcu; /* 56 */
00116         struct __attribute__((__packed__))
00117         {
00118             char __pre_pad[2];
00119             L4_ktrace_t__Mword id; /* 36+4 */
00120             L4_ktrace_t__Mword mask; /* 40+4 */
00121             L4_ktrace_t__Mword fpage; /* 44+4 */
00122             char map; /* 48+1 */
00123         } tmap; /* 56 */
00124         struct __attribute__((__packed__))

```

```

00125     {
00126         char __pre_pad[2];
00127         L4_ktrace_t__Address _address; /* 36+4 */
00128         int _len; /* 40+4 */
00129         L4_ktrace_t__Mword _value; /* 44+4 */
00130         int _mode; /* 48+4 */
00131     } bp; /* 56 */
00132     struct __attribute__((__packed__))
00133     {
00134         char __pre_pad[2];
00135         L4_ktrace_t__Context *dst; /* 36+4 */
00136         L4_ktrace_t__Context *dst_orig; /* 40+4 */
00137         L4_ktrace_t__Address kernel_ip; /* 44+4 */
00138         L4_ktrace_t__Mword lock_cnt; /* 48+4 */
00139         L4_ktrace_t__Space *from_space; /* 52+4 */
00140         L4_ktrace_t__Sched_context *from_sched; /* 56+4 */
00141         L4_ktrace_t__Mword from_prio; /* 60+4 */
00142     } context_switch; /* 64 */
00143     struct __attribute__((__packed__))
00144     {
00145     } empty; /* 40 */
00146     struct __attribute__((__packed__))
00147     {
00148         char __pre_pad[2];
00149         L4_ktrace_t__L4_msg_tag _tag; /* 36+4 */
00150         L4_ktrace_t__Mword _dword[2]; /* 40+8 */
00151         L4_ktrace_t__L4_obj_ref _dst; /* 48+4 */
00152         L4_ktrace_t__Mword _dbg_id; /* 52+4 */
00153         L4_ktrace_t__Mword _label; /* 56+4 */
00154         L4_ktrace_t__L4_timeout_pair _timeout; /* 60+4 */
00155     } ipc; /* 64 */
00156     struct __attribute__((__packed__))
00157     {
00158         L4_ktrace_t__Unsigned8 _have_snd; /* 34+1 */
00159         L4_ktrace_t__Unsigned8 _is_np; /* 35+1 */
00160         L4_ktrace_t__L4_msg_tag _tag; /* 36+4 */
00161         L4_ktrace_t__Mword _dword[2]; /* 40+8 */
00162         L4_ktrace_t__L4_error _result; /* 48+4 */
00163         L4_ktrace_t__Mword _from; /* 52+4 */
00164         L4_ktrace_t__L4_obj_ref _dst; /* 56+4 */
00165         L4_ktrace_t__Mword _pair_event; /* 60+4 */
00166     } ipc_res; /* 64 */
00167     struct __attribute__((__packed__))
00168     {
00169         char __pre_pad[2];
00170         union __attribute__((__packed__)) {
00171             char msg[24]; /* 0+24 */
00172             struct __attribute__((__packed__)) {
00173                 char tag[2]; /* 0+2 */
00174                 char __pad_l[2];
00175                 char *ptr; /* 4+4 */
00176             } mptr; /* 0+8 */
00177             } msg; /* 36+24 */
00178         } ke; /* 64 */
00179     } struct __attribute__((__packed__))
00180     {
00181         char _msg[24]; /* 34+24 */
00182     } ke_bin; /* 64 */
00183     struct __attribute__((__packed__))
00184     {
00185         char __pre_pad[2];
00186         L4_ktrace_t__Mword v[3]; /* 36+12 */
00187         union __attribute__((__packed__)) {
00188             char msg[12]; /* 0+12 */
00189             struct __attribute__((__packed__)) {
00190                 char tag[2]; /* 0+2 */
00191                 char __pad_l[2];
00192                 char *ptr; /* 4+4 */
00193             } mptr; /* 0+8 */
00194             } msg; /* 48+12 */
00195         } ke_reg; /* 64 */
00196     } struct __attribute__((__packed__))
00197     {
00198         char __pre_pad[2];
00199         L4_ktrace_t__Address _pfa; /* 36+4 */
00200         L4_ktrace_t__Mword _error; /* 40+4 */
00201         L4_ktrace_t__Space *_space; /* 44+4 */
00202     } pf; /* 48 */
00203     struct __attribute__((__packed__))
00204     {
00205         unsigned short mode; /* 34+2 */
00206         L4_ktrace_t__Context *owner; /* 36+4 */
00207         unsigned short id; /* 40+2 */
00208         unsigned short prio; /* 42+2 */
00209         long left; /* 44+4 */
00210         unsigned long quantum; /* 48+4 */
00211     } sched; /* 56 */

```

```

00212     struct __attribute__((__packed__))
00213     {
00214         char __pre_pad[2];
00215         L4_ktrace_t__Unsigned32 _error; /* 36+4 */
00216         L4_ktrace_t__Mword _cpsr; /* 40+4 */
00217         L4_ktrace_t__Mword _sp; /* 44+4 */
00218     } trap; /* 48 */
00219     struct __attribute__((__packed__))
00220     {
00221         char _padding[24]; /* 34+24 */
00222         char __post_pad[6]; /* 58+6 */
00223     } fullsize; /* 64 */
00224     struct __attribute__((__packed__))
00225     {
00226         char __pre_pad[2];
00227         L4_ktrace_t__Cap_index cap_idx; /* 36+4 */
00228     } ieh; /* 40 */
00229     struct __attribute__((__packed__))
00230     {
00231         char __pre_pad[2];
00232         L4_ktrace_t__Mword pfa; /* 36+4 */
00233         L4_ktrace_t__Cap_index cap_idx; /* 40+4 */
00234         L4_ktrace_t__Mword err; /* 44+4 */
00235     } ipfh; /* 48 */
00236     struct __attribute__((__packed__))
00237     {
00238         char __pre_pad[2];
00239         L4_ktrace_t__Mword id; /* 36+4 */
00240         L4_ktrace_t__Mword ip; /* 40+4 */
00241         L4_ktrace_t__Mword sp; /* 44+4 */
00242         L4_ktrace_t__Mword op; /* 48+4 */
00243     } exregs; /* 56 */
00244     struct __attribute__((__packed__))
00245     {
00246         char __pre_pad[2];
00247         L4_ktrace_t__Mword state; /* 36+4 */
00248         L4_ktrace_t__Address user_ip; /* 40+4 */
00249         L4_ktrace_t__Cpu_number src_cpu; /* 44+4 */
00250         L4_ktrace_t__Cpu_number target_cpu; /* 48+4 */
00251     } migration; /* 56 */
00252     struct __attribute__((__packed__))
00253     {
00254         char __pre_pad[2];
00255         L4_ktrace_t__Address user_ip; /* 36+4 */
00256     } timer; /* 40 */
00257     } m;
00258 } l4_tracebuffer_entry_t;

```

## 16.104 ktrace\_events.h

```

00001 /* Note, automatically generated from Fiasco binary */
00002 #pragma once
00003
00004 enum L4_ktrace_tbuf_entry_fixed
00005 {
00006     l4_ktrace_tbuf_unused = 0,
00007     l4_ktrace_tbuf_pf = 1,
00008     l4_ktrace_tbuf_ipc = 2,
00009     l4_ktrace_tbuf_ipc_res = 3,
00010     l4_ktrace_tbuf_ipc_trace = 4,
00011     l4_ktrace_tbuf_ke = 5,
00012     l4_ktrace_tbuf_ke_reg = 6,
00013     l4_ktrace_tbuf_breakpoint = 7,
00014     l4_ktrace_tbuf_ke_bin = 8,
00015     l4_ktrace_tbuf_dynentries = 9,
00016     l4_ktrace_tbuf_max = 128,
00017     l4_ktrace_tbuf_hidden = 128,
00018 };
00019
00020 typedef unsigned long L4_ktrace_t__Address;
00021 typedef unsigned long L4_ktrace_t__Cap_index;
00022 typedef void L4_ktrace_t__Context;
00023 typedef void L4_ktrace_t__Context__Drq;
00024 typedef unsigned L4_ktrace_t__Context__Drq_log__Type;
00025 typedef unsigned L4_ktrace_t__Cpu_number;
00026 typedef void L4_ktrace_t__Irq_base;
00027 typedef void L4_ktrace_t__Irq_chip;
00028 typedef void L4_ktrace_t__Kobject;
00029 typedef unsigned long L4_ktrace_t__L4_error;
00030 typedef unsigned long L4_ktrace_t__L4_msg_tag;
00031 typedef unsigned long L4_ktrace_t__L4_obj_ref;
00032 typedef unsigned L4_ktrace_t__L4_timeout_pair;
00033 typedef unsigned long L4_ktrace_t__Mword;

```



```

00034 typedef void L4_ktrace_t__Rcu_item;
00035 typedef void L4_ktrace_t__Sched_context;
00036 typedef long L4_ktrace_t__Smword;
00037 typedef void L4_ktrace_t__Space;
00038 typedef unsigned int L4_ktrace_t__Unsigned32;
00039 typedef unsigned long long L4_ktrace_t__Unsigned64;
00040 typedef unsigned char L4_ktrace_t__Unsigned8;
00041 typedef void L4_ktrace_t__cxx__Type_info;
00042
00043 typedef struct __attribute__((packed))
00044 {
00045     L4_ktrace_t__Mword _number; /* 0+8 */
00046     L4_ktrace_t__Address _ip; /* 8+8 */
00047     L4_ktrace_t__Unsigned64 _tsc; /* 16+8 */
00048     L4_ktrace_t__Context *_ctx; /* 24+8 */
00049     L4_ktrace_t__Unsigned32 _pmc1; /* 32+4 */
00050     L4_ktrace_t__Unsigned32 _pmc2; /* 36+4 */
00051     L4_ktrace_t__Unsigned32 _kclock; /* 40+4 */
00052     L4_ktrace_t__Unsigned8 _type; /* 44+1 */
00053     L4_ktrace_t__Unsigned8 _cpu; /* 45+1 */
00054     union __attribute__((__packed__))
00055     {
00056         struct __attribute__((__packed__))
00057         {
00058             char __pre_pad[2];
00059             void *func; /* 48+8 */
00060             L4_ktrace_t__Context *thread; /* 56+8 */
00061             L4_ktrace_t__Context__Drq *rq; /* 64+8 */
00062             L4_ktrace_t__Cpu_number target_cpu; /* 72+4 */
00063             L4_ktrace_t__Context__Drq_log__Type type; /* 76+4 */
00064             char wait; /* 80+1 */
00065         } drq; /* 88 */
00066         struct __attribute__((__packed__))
00067         {
00068             char __pre_pad[2];
00069             L4_ktrace_t__Mword state; /* 48+8 */
00070             L4_ktrace_t__Mword ip; /* 56+8 */
00071             L4_ktrace_t__Mword sp; /* 64+8 */
00072             L4_ktrace_t__Mword space; /* 72+8 */
00073             L4_ktrace_t__Mword err; /* 80+8 */
00074             unsigned char type; /* 88+1 */
00075             unsigned char trap; /* 89+1 */
00076         } vcpu; /* 96 */
00077         struct __attribute__((__packed__))
00078         {
00079             char __pre_pad[2];
00080             L4_ktrace_t__Smword op; /* 48+8 */
00081             L4_ktrace_t__Cap_index buffer; /* 56+8 */
00082             L4_ktrace_t__Mword id; /* 64+8 */
00083             L4_ktrace_t__Mword ram; /* 72+8 */
00084             L4_ktrace_t__Mword newo; /* 80+8 */
00085         } factory; /* 88 */
00086         struct __attribute__((__packed__))
00087         {
00088             char __pre_pad[2];
00089             L4_ktrace_t__Mword gate_dbg_id; /* 48+8 */
00090             L4_ktrace_t__Mword thread_dbg_id; /* 56+8 */
00091             L4_ktrace_t__Mword label; /* 64+8 */
00092         } gate; /* 72 */
00093         struct __attribute__((__packed__))
00094         {
00095             char __pre_pad[2];
00096             L4_ktrace_t__Irq_base *obj; /* 48+8 */
00097             L4_ktrace_t__Irq_chip *chip; /* 56+8 */
00098             L4_ktrace_t__Mword pin; /* 64+8 */
00099         } irq; /* 72 */
00100         struct __attribute__((__packed__))
00101         {
00102             char __pre_pad[2];
00103             L4_ktrace_t__Kobject *obj; /* 48+8 */
00104             L4_ktrace_t__Mword id; /* 56+8 */
00105             L4_ktrace_t__cxx__Type_info *type; /* 64+8 */
00106             L4_ktrace_t__Mword ram; /* 72+8 */
00107         } destroy; /* 80 */
00108         struct __attribute__((__packed__))
00109         {
00110             char __pre_pad[2];
00111             L4_ktrace_t__Cpu_number cpu; /* 48+4 */
00112             char __pad_l[4];
00113             L4_ktrace_t__Rcu_item *item; /* 56+8 */
00114             void *cb; /* 64+8 */
00115             unsigned char event; /* 72+1 */
00116         } rcu; /* 80 */
00117         struct __attribute__((__packed__))
00118         {
00119             char __pre_pad[2];
00120             L4_ktrace_t__Mword id; /* 48+8 */

```

```

00121     L4_ktrace_t__Mword mask; /* 56+8 */
00122     L4_ktrace_t__Mword fpage; /* 64+8 */
00123     char map; /* 72+1 */
00124 } tmap; /* 80 */
00125 struct __attribute__((__packed__))
00126 {
00127     char __pre_pad[2];
00128     L4_ktrace_t__Address _address; /* 48+8 */
00129     int _len; /* 56+4 */
00130     char __pad_1[4];
00131     L4_ktrace_t__Mword _value; /* 64+8 */
00132     int _mode; /* 72+4 */
00133 } bp; /* 80 */
00134 struct __attribute__((__packed__))
00135 {
00136     char __pre_pad[2];
00137     L4_ktrace_t__Context *dst; /* 48+8 */
00138     L4_ktrace_t__Context *dst_orig; /* 56+8 */
00139     L4_ktrace_t__Address kernel_ip; /* 64+8 */
00140     L4_ktrace_t__Mword lock_cnt; /* 72+8 */
00141     L4_ktrace_t__Space *from_space; /* 80+8 */
00142     L4_ktrace_t__Sched_context *from_sched; /* 88+8 */
00143     L4_ktrace_t__Mword from_prio; /* 96+8 */
00144 } context_switch; /* 104 */
00145 struct __attribute__((__packed__))
00146 {
00147 } empty; /* 48 */
00148 struct __attribute__((__packed__))
00149 {
00150     char __pre_pad[2];
00151     L4_ktrace_t__L4_msg_tag _tag; /* 48+8 */
00152     L4_ktrace_t__Mword _dword[2]; /* 56+16 */
00153     L4_ktrace_t__L4_obj_ref _dst; /* 72+8 */
00154     L4_ktrace_t__Mword _dbg_id; /* 80+8 */
00155     L4_ktrace_t__Mword _label; /* 88+8 */
00156     L4_ktrace_t__L4_timeout_pair _timeout; /* 96+4 */
00157     char __pad_1[4];
00158     L4_ktrace_t__Unsigned64 _to_abs_rcv; /* 104+8 */
00159 } ipc; /* 112 */
00160 struct __attribute__((__packed__))
00161 {
00162     L4_ktrace_t__Unsigned8 _have_snd; /* 46+1 */
00163     L4_ktrace_t__Unsigned8 _is_np; /* 47+1 */
00164     L4_ktrace_t__L4_msg_tag _tag; /* 48+8 */
00165     L4_ktrace_t__Mword _dword[2]; /* 56+16 */
00166     L4_ktrace_t__L4_error_result; /* 72+8 */
00167     L4_ktrace_t__Mword _from; /* 80+8 */
00168     L4_ktrace_t__L4_obj_ref _dst; /* 88+8 */
00169     L4_ktrace_t__Mword _pair_event; /* 96+8 */
00170 } ipc_res; /* 104 */
00171 struct __attribute__((__packed__))
00172 {
00173     char __pre_pad[2];
00174     union __attribute__((__packed__)) {
00175         char msg[80]; /* 0+80 */
00176         struct __attribute__((__packed__)) {
00177             char tag[2]; /* 0+2 */
00178             char __pad_1[6];
00179             char *ptr; /* 8+8 */
00180         } mptr; /* 0+16 */
00181     } msg; /* 48+80 */
00182 } ke; /* 128 */
00183 struct __attribute__((__packed__))
00184 {
00185     char _msg[80]; /* 46+80 */
00186 } ke_bin; /* 128 */
00187 struct __attribute__((__packed__))
00188 {
00189     char __pre_pad[2];
00190     L4_ktrace_t__Mword v[3]; /* 48+24 */
00191     union __attribute__((__packed__)) {
00192         char msg[56]; /* 0+56 */
00193         struct __attribute__((__packed__)) {
00194             char tag[2]; /* 0+2 */
00195             char __pad_1[6];
00196             char *ptr; /* 8+8 */
00197         } mptr; /* 0+16 */
00198     } msg; /* 72+56 */
00199 } ke_reg; /* 128 */
00200 struct __attribute__((__packed__))
00201 {
00202     char __pre_pad[2];
00203     L4_ktrace_t__Address _pfa; /* 48+8 */
00204     L4_ktrace_t__Mword _error; /* 56+8 */
00205     L4_ktrace_t__Space *_space; /* 64+8 */
00206 } pf; /* 72 */
00207 struct __attribute__((__packed__))

```

```

00208     {
00209         unsigned short mode; /* 46+2 */
00210         L4_ktrace_t__Context *owner; /* 48+8 */
00211         unsigned short id; /* 56+2 */
00212         unsigned short prio; /* 58+2 */
00213         char __pad_l[4];
00214         long left; /* 64+8 */
00215         unsigned long quantum; /* 72+8 */
00216     } sched; /* 80 */
00217     struct __attribute__((__packed__))
00218     {
00219         char __pre_pad[2];
00220         L4_ktrace_t__Unsigned32 _error; /* 48+4 */
00221         char __pad_l[4];
00222         L4_ktrace_t__Mword _cpsr; /* 56+8 */
00223         L4_ktrace_t__Mword _sp; /* 64+8 */
00224     } trap; /* 72 */
00225     struct __attribute__((__packed__))
00226     {
00227         char _padding[80]; /* 46+80 */
00228         char __post_pad[2]; /* 126+2 */
00229     } fullsize; /* 128 */
00230     struct __attribute__((__packed__))
00231     {
00232         char __pre_pad[2];
00233         L4_ktrace_t__Cap_index cap_idx; /* 48+8 */
00234     } ieh; /* 56 */
00235     struct __attribute__((__packed__))
00236     {
00237         char __pre_pad[2];
00238         L4_ktrace_t__Mword pfa; /* 48+8 */
00239         L4_ktrace_t__Cap_index cap_idx; /* 56+8 */
00240         L4_ktrace_t__Mword err; /* 64+8 */
00241     } ipfh; /* 72 */
00242     struct __attribute__((__packed__))
00243     {
00244         char __pre_pad[2];
00245         L4_ktrace_t__Mword id; /* 48+8 */
00246         L4_ktrace_t__Mword ip; /* 56+8 */
00247         L4_ktrace_t__Mword sp; /* 64+8 */
00248         L4_ktrace_t__Mword op; /* 72+8 */
00249     } exregs; /* 80 */
00250     struct __attribute__((__packed__))
00251     {
00252         char __pre_pad[2];
00253         L4_ktrace_t__Mword state; /* 48+8 */
00254         L4_ktrace_t__Address user_ip; /* 56+8 */
00255         L4_ktrace_t__Cpu_number src_cpu; /* 64+4 */
00256         L4_ktrace_t__Cpu_number target_cpu; /* 68+4 */
00257     } migration; /* 72 */
00258     struct __attribute__((__packed__))
00259     {
00260         char __pre_pad[2];
00261         L4_ktrace_t__Address user_ip; /* 48+8 */
00262     } timer; /* 56 */
00263     } m;
00264 } l4_tracebuffer_entry_t;

```

## 16.105 ktrace\_events.h

```

00001 /* Note, automatically generated from Fiasco binary */
00002 #pragma once
00003
00004 enum L4_ktrace_tbuf_entry_fixed
00005 {
00006     l4_ktrace_tbuf_unused = 0,
00007     l4_ktrace_tbuf_pf = 1,
00008     l4_ktrace_tbuf_ipc = 2,
00009     l4_ktrace_tbuf_ipc_res = 3,
00010     l4_ktrace_tbuf_ipc_trace = 4,
00011     l4_ktrace_tbuf_ke = 5,
00012     l4_ktrace_tbuf_ke_reg = 6,
00013     l4_ktrace_tbuf_breakpoint = 7,
00014     l4_ktrace_tbuf_ke_bin = 8,
00015     l4_ktrace_tbuf_dynentries = 9,
00016     l4_ktrace_tbuf_max = 128,
00017     l4_ktrace_tbuf_hidden = 128,
00018 };
00019
00020 typedef unsigned long L4_ktrace_t__Address;
00021 typedef unsigned long L4_ktrace_t__Cap_index;
00022 typedef void L4_ktrace_t__Context;
00023 typedef void L4_ktrace_t__Context__Drq;

```

```

00024 typedef unsigned L4_ktrace_t__Context__Drq_log__Type;
00025 typedef unsigned L4_ktrace_t__Cpu_number;
00026 typedef void L4_ktrace_t__Irq_base;
00027 typedef void L4_ktrace_t__Irq_chip;
00028 typedef void L4_ktrace_t__Kobject;
00029 typedef unsigned long L4_ktrace_t__L4_error;
00030 typedef unsigned long L4_ktrace_t__L4_msg_tag;
00031 typedef unsigned long L4_ktrace_t__L4_obj_ref;
00032 typedef unsigned L4_ktrace_t__L4_timeout_pair;
00033 typedef unsigned long L4_ktrace_t__Mword;
00034 typedef void L4_ktrace_t__Rcu_item;
00035 typedef void L4_ktrace_t__Sched_context;
00036 typedef long L4_ktrace_t__Smword;
00037 typedef void L4_ktrace_t__Space;
00038 typedef unsigned short L4_ktrace_t__Unsigned16;
00039 typedef unsigned int L4_ktrace_t__Unsigned32;
00040 typedef unsigned long long L4_ktrace_t__Unsigned64;
00041 typedef unsigned char L4_ktrace_t__Unsigned8;
00042 typedef void L4_ktrace_t__cxx__Type_info;
00043
00044 typedef struct __attribute__((packed))
00045 {
00046     L4_ktrace_t__Mword _number; /* 0+4 */
00047     L4_ktrace_t__Address _ip; /* 4+4 */
00048     L4_ktrace_t__Unsigned64 _tsc; /* 8+8 */
00049     L4_ktrace_t__Context *_ctx; /* 16+4 */
00050     L4_ktrace_t__Unsigned32 _pmc1; /* 20+4 */
00051     L4_ktrace_t__Unsigned32 _pmc2; /* 24+4 */
00052     L4_ktrace_t__Unsigned32 _kclock; /* 28+4 */
00053     L4_ktrace_t__Unsigned8 _type; /* 32+1 */
00054     L4_ktrace_t__Unsigned8 _cpu; /* 33+1 */
00055     union __attribute__((__packed__))
00056     {
00057         struct __attribute__((__packed__))
00058         {
00059             char __pre_pad[2];
00060             void *func; /* 36+4 */
00061             L4_ktrace_t__Context *thread; /* 40+4 */
00062             L4_ktrace_t__Context__Drq *rq; /* 44+4 */
00063             L4_ktrace_t__Cpu_number target_cpu; /* 48+4 */
00064             L4_ktrace_t__Context__Drq_log__Type type; /* 52+4 */
00065             char wait; /* 56+1 */
00066         } drq; /* 64 */
00067         struct __attribute__((__packed__))
00068         {
00069             char __pre_pad[2];
00070             L4_ktrace_t__Mword state; /* 36+4 */
00071             L4_ktrace_t__Mword ip; /* 40+4 */
00072             L4_ktrace_t__Mword sp; /* 44+4 */
00073             L4_ktrace_t__Mword space; /* 48+4 */
00074             L4_ktrace_t__Mword err; /* 52+4 */
00075             unsigned char type; /* 56+1 */
00076             unsigned char trap; /* 57+1 */
00077         } vcpu; /* 64 */
00078         struct __attribute__((__packed__))
00079         {
00080             char __pre_pad[2];
00081             L4_ktrace_t__Smword op; /* 36+4 */
00082             L4_ktrace_t__Cap_index buffer; /* 40+4 */
00083             L4_ktrace_t__Mword id; /* 44+4 */
00084             L4_ktrace_t__Mword ram; /* 48+4 */
00085             L4_ktrace_t__Mword newo; /* 52+4 */
00086         } factory; /* 56 */
00087         struct __attribute__((__packed__))
00088         {
00089             char __pre_pad[2];
00090             L4_ktrace_t__Mword gate_dbg_id; /* 36+4 */
00091             L4_ktrace_t__Mword thread_dbg_id; /* 40+4 */
00092             L4_ktrace_t__Mword label; /* 44+4 */
00093         } gate; /* 48 */
00094         struct __attribute__((__packed__))
00095         {
00096             char __pre_pad[2];
00097             L4_ktrace_t__Irq_base *obj; /* 36+4 */
00098             L4_ktrace_t__Irq_chip *chip; /* 40+4 */
00099             L4_ktrace_t__Mword pin; /* 44+4 */
00100         } irq; /* 48 */
00101         struct __attribute__((__packed__))
00102         {
00103             char __pre_pad[2];
00104             L4_ktrace_t__Kobject *obj; /* 36+4 */
00105             L4_ktrace_t__Mword id; /* 40+4 */
00106             L4_ktrace_t__cxx__Type_info *type; /* 44+4 */
00107             L4_ktrace_t__Mword ram; /* 48+4 */
00108         } destroy; /* 56 */
00109         struct __attribute__((__packed__))
00110         {

```

```

00111     char __pre_pad[2];
00112     L4_ktrace_t__Cpu_number cpu; /* 36+4 */
00113     L4_ktrace_t__Rcu_item *item; /* 40+4 */
00114     void *cb; /* 44+4 */
00115     unsigned char event; /* 48+1 */
00116 } rcu; /* 56 */
00117 struct __attribute__((__packed__))
00118 {
00119     char __pre_pad[2];
00120     L4_ktrace_t__Mword id; /* 36+4 */
00121     L4_ktrace_t__Mword mask; /* 40+4 */
00122     L4_ktrace_t__Mword fpage; /* 44+4 */
00123     char map; /* 48+1 */
00124 } tmap; /* 56 */
00125 struct __attribute__((__packed__))
00126 {
00127     char __pre_pad[2];
00128     L4_ktrace_t__Address _address; /* 36+4 */
00129     int _len; /* 40+4 */
00130     L4_ktrace_t__Mword _value; /* 44+4 */
00131     int _mode; /* 48+4 */
00132 } bp; /* 56 */
00133 struct __attribute__((__packed__))
00134 {
00135     char __pre_pad[2];
00136     L4_ktrace_t__Context *dst; /* 36+4 */
00137     L4_ktrace_t__Context *dst_orig; /* 40+4 */
00138     L4_ktrace_t__Address kernel_ip; /* 44+4 */
00139     L4_ktrace_t__Mword lock_cnt; /* 48+4 */
00140     L4_ktrace_t__Space *from_space; /* 52+4 */
00141     L4_ktrace_t__Sched_context *from_sched; /* 56+4 */
00142     L4_ktrace_t__Mword from_prio; /* 60+4 */
00143 } context_switch; /* 64 */
00144 struct __attribute__((__packed__))
00145 {
00146 } empty; /* 40 */
00147 struct __attribute__((__packed__))
00148 {
00149     char __pre_pad[2];
00150     L4_ktrace_t__L4_msg_tag _tag; /* 36+4 */
00151     L4_ktrace_t__Mword _dword[2]; /* 40+8 */
00152     L4_ktrace_t__L4_obj_ref _dst; /* 48+4 */
00153     L4_ktrace_t__Mword _dbg_id; /* 52+4 */
00154     L4_ktrace_t__Mword _label; /* 56+4 */
00155     L4_ktrace_t__L4_timeout_pair _timeout; /* 60+4 */
00156 } ipc; /* 64 */
00157 struct __attribute__((__packed__))
00158 {
00159     L4_ktrace_t__Unsigned8 _have_snd; /* 34+1 */
00160     L4_ktrace_t__Unsigned8 _is_np; /* 35+1 */
00161     L4_ktrace_t__L4_msg_tag _tag; /* 36+4 */
00162     L4_ktrace_t__Mword _dword[2]; /* 40+8 */
00163     L4_ktrace_t__L4_error _result; /* 48+4 */
00164     L4_ktrace_t__Mword _from; /* 52+4 */
00165     L4_ktrace_t__L4_obj_ref _dst; /* 56+4 */
00166     L4_ktrace_t__Mword _pair_event; /* 60+4 */
00167 } ipc_res; /* 64 */
00168 struct __attribute__((__packed__))
00169 {
00170     char __pre_pad[2];
00171     union __attribute__((__packed__)) {
00172         char msg[24]; /* 0+24 */
00173         struct __attribute__((__packed__)) {
00174             char tag[2]; /* 0+2 */
00175             char __pad_1[2];
00176             char *ptr; /* 4+4 */
00177         } mptr; /* 0+8 */
00178     } msg; /* 36+24 */
00179 } ke; /* 64 */
00180 struct __attribute__((__packed__))
00181 {
00182     char _msg[24]; /* 34+24 */
00183 } ke_bin; /* 64 */
00184 struct __attribute__((__packed__))
00185 {
00186     char __pre_pad[2];
00187     L4_ktrace_t__Mword v[3]; /* 36+12 */
00188     union __attribute__((__packed__)) {
00189         char msg[12]; /* 0+12 */
00190         struct __attribute__((__packed__)) {
00191             char tag[2]; /* 0+2 */
00192             char __pad_1[2];
00193             char *ptr; /* 4+4 */
00194         } mptr; /* 0+8 */
00195     } msg; /* 48+12 */
00196 } ke_reg; /* 64 */
00197 struct __attribute__((__packed__))

```

```

00198     {
00199         char __pre_pad[2];
00200         L4_ktrace_t__Address _pfa; /* 36+4 */
00201         L4_ktrace_t__Mword _error; /* 40+4 */
00202         L4_ktrace_t__Space *_space; /* 44+4 */
00203     } pf; /* 48 */
00204     struct __attribute__((__packed__))
00205     {
00206         unsigned short mode; /* 34+2 */
00207         L4_ktrace_t__Context *owner; /* 36+4 */
00208         unsigned short id; /* 40+2 */
00209         unsigned short prio; /* 42+2 */
00210         long left; /* 44+4 */
00211         unsigned long quantum; /* 48+4 */
00212     } sched; /* 56 */
00213     struct __attribute__((__packed__))
00214     {
00215         L4_ktrace_t__Unsigned8 _trapno; /* 34+1 */
00216         char __pad_1[1];
00217         L4_ktrace_t__Unsigned16 _error; /* 36+2 */
00218         char __pad_2[2];
00219         L4_ktrace_t__Mword _ebp; /* 40+4 */
00220         L4_ktrace_t__Mword _cr2; /* 44+4 */
00221         L4_ktrace_t__Mword _eax; /* 48+4 */
00222         L4_ktrace_t__Mword _eflags; /* 52+4 */
00223         L4_ktrace_t__Mword _esp; /* 56+4 */
00224         L4_ktrace_t__Unsigned16 _cs; /* 60+2 */
00225         L4_ktrace_t__Unsigned16 _ds; /* 62+2 */
00226     } trap; /* 64 */
00227     struct __attribute__((__packed__))
00228     {
00229         char __padding[24]; /* 34+24 */
00230         char __post_pad[6]; /* 58+6 */
00231     } fullsize; /* 64 */
00232     struct __attribute__((__packed__))
00233     {
00234         char __pre_pad[2];
00235         L4_ktrace_t__Cap_index cap_idx; /* 36+4 */
00236     } ieh; /* 40 */
00237     struct __attribute__((__packed__))
00238     {
00239         char __pre_pad[2];
00240         L4_ktrace_t__Mword pfa; /* 36+4 */
00241         L4_ktrace_t__Cap_index cap_idx; /* 40+4 */
00242         L4_ktrace_t__Mword err; /* 44+4 */
00243     } ipfh; /* 48 */
00244     struct __attribute__((__packed__))
00245     {
00246         char __pre_pad[2];
00247         L4_ktrace_t__Mword id; /* 36+4 */
00248         L4_ktrace_t__Mword ip; /* 40+4 */
00249         L4_ktrace_t__Mword sp; /* 44+4 */
00250         L4_ktrace_t__Mword op; /* 48+4 */
00251     } exregs; /* 56 */
00252     struct __attribute__((__packed__))
00253     {
00254         char __pre_pad[2];
00255         L4_ktrace_t__Mword state; /* 36+4 */
00256         L4_ktrace_t__Address user_ip; /* 40+4 */
00257         L4_ktrace_t__Cpu_number src_cpu; /* 44+4 */
00258         L4_ktrace_t__Cpu_number target_cpu; /* 48+4 */
00259     } migration; /* 56 */
00260     struct __attribute__((__packed__))
00261     {
00262         char __pre_pad[2];
00263         L4_ktrace_t__Address user_ip; /* 36+4 */
00264     } timer; /* 40 */
00265     struct __attribute__((__packed__))
00266     {
00267         char __pre_pad[2];
00268         L4_ktrace_t__Mword exitcode; /* 36+4 */
00269         L4_ktrace_t__Mword exitinfo1; /* 40+4 */
00270         L4_ktrace_t__Mword exitinfo2; /* 44+4 */
00271         L4_ktrace_t__Mword rip; /* 48+4 */
00272     } svm; /* 56 */
00273     } m;
00274 } l4_tracebuffer_entry_t;

```

## 16.106 amd64/l4/sys/linkage.h File Reference

Linkage.

**Macros**

- **#define L4\_CV**  
*Define calling convention.*

**16.106.1 Detailed Description**

Linkage.

Definition in file [linkage.h](#).

**16.107 linkage.h**

[Go to the documentation of this file.](#)

```

00001
00006 /*
00007  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00008  *                Alexander Warg <warg@os.inf.tu-dresden.de>,
00009  *                Torsten Frenzel <frenzel@os.inf.tu-dresden.de>
00010  *                economic rights: Technische Universität Dresden (Germany)
00011  *
00012  * License: see LICENSE.spdx (in this directory or the directories above)
00013  */
00014 #ifndef __L4__SYS__ARCH_AMD64__LINKAGE_H__
00015 #define __L4__SYS__ARCH_AMD64__LINKAGE_H__
00016
00017 #ifdef __ASSEMBLY__
00018
00019 #ifndef ENTRY
00020 #define ENTRY(name) \
00021     .globl name; \
00022     .p2align(2); \
00023     name:
00024
00025 #endif /* __ASSEMBLY__ */
00026 #endif /* ! ENTRY */
00027
00028 #define L4_FASTCALL(x)      x
00029 #define l4_fastcall
00030
00036 #define L4_CV
00037
00038 #endif /* ! __L4__SYS__ARCH_AMD64__LINKAGE_H__ */

```

**16.108 arm/l4/sys/linkage.h File Reference**

Linkage.

**Macros**

- **#define L4\_CV**  
*Define calling convention.*

**16.108.1 Detailed Description**

Linkage.

Definition in file [linkage.h](#).

## 16.109 linkage.h

[Go to the documentation of this file.](#)

```

00001
00006 /*
00007  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00008  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00009  *      economic rights: Technische Universität Dresden (Germany)
00010  *
00011  * License: see LICENSE.spdx (in this directory or the directories above)
00012  */
00013 #ifndef __L4__SYS__ARCH_ARM__LINKAGE_H__
00014 #define __L4__SYS__ARCH_ARM__LINKAGE_H__
00015
00016 #ifdef __ASSEMBLY__
00017 #ifndef ENTRY
00018 #define ENTRY(name) \
00019     .globl name; \
00020     .p2align(2); \
00021     name:
00022 #endif
00023 #endif
00024
00025 #define L4_FASTCALL(x)  x
00026 #define l4_fastcall
00027
00033 #define L4_CV
00034
00035 #ifdef __PIC__
00036 # define L4_LONG_CALL
00037 #else
00038 # define L4_LONG_CALL __attribute__((long_call))
00039 #endif
00040
00041 #endif /* ! __L4__SYS__ARCH_ARM__LINKAGE_H__ */

```

## 16.110 linkage.h

```

00001 #pragma once
00002
00008 #define L4_CV
00009
00010 #define L4_FASTCALL(x)  x
00011 #define l4_fastcall

```

## 16.111 x86/I4/sys/linkage.h File Reference

Linkage.

### Macros

- **#define L4\_CV**  
*Define calling convention.*

### 16.111.1 Detailed Description

Linkage.

Definition in file [linkage.h](#).



## 16.112 linkage.h

[Go to the documentation of this file.](#)

```

00001
00006 /*
00007  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00008  *      Alexander Warg <warg@os.inf.tu-dresden.de>,
00009  *      Frank Mehnert <fm3@os.inf.tu-dresden.de>
00010  *      economic rights: Technische Universität Dresden (Germany)
00011  *
00012  * License: see LICENSE.spdx (in this directory or the directories above)
00013  */
00014 #ifndef __L4__SYS__ARCH_X86__LINKAGE_H__
00015 #define __L4__SYS__ARCH_X86__LINKAGE_H__
00016
00017 #ifdef __ASSEMBLY__
00018
00019 #ifndef ENTRY
00020 #define ENTRY(name) \
00021     .globl name; \
00022     .p2align(2); \
00023     name:
00024
00025 #endif /* ! ENTRY */
00026 #endif /* __ASSEMBLY__ */
00027
00028 #define L4_FASTCALL(x)  x __attribute__((regparm(3)))
00029 #define l4_fastcall __attribute__((regparm(3)))
00030
00036 #define L4_CV  __attribute__((regparm(0)))
00037
00038 #endif /* ! __L4__SYS__ARCH_X86__LINKAGE_H__ */

```


## 16.113 arm/l4/sys/mem\_op.h File Reference

Memory access functions (ARM specific).

```
#include <l4/sys/compiler.h>
```

```
#include <l4/sys/syscall_defs.h>
```

Include dependency graph for mem\_op.h:



### Enumerations

- enum `L4_mem_op_widths` { `L4_MEM_WIDTH_1BYTE` = 0, `L4_MEM_WIDTH_2BYTE` = 1, `L4_MEM_WIDTH_4BYTE` = 2 }

*Memory access width definitions.*

## Functions

- unsigned long [l4\\_mem\\_read](#) (unsigned long virtaddress, unsigned width)  
*Read user task memory from kernel privilege level.*
- void [l4\\_mem\\_write](#) (unsigned long virtaddress, unsigned width, unsigned long value)  
*Write user task memory from kernel privilege level.*
- unsigned long [l4\\_mem\\_arm\\_op\\_call](#) (unsigned long op, unsigned long va, unsigned long width, unsigned long value)  
*Implementations.*

### 16.113.1 Detailed Description

Memory access functions (ARM specific).

#### Date

2010-10

#### Author

Adam Lackorzynski [adam@os.inf.tu-dresden.de](mailto:adam@os.inf.tu-dresden.de)

Definition in file [mem\\_op.h](#).

## 16.114 mem\_op.h

[Go to the documentation of this file.](#)

```

00001
00009 /*
00010  * (c) 2010 Author(s)
00011  *      economic rights: Technische Universität Dresden (Germany)
00012  *
00013  * License: see LICENSE.spdx (in this directory or the directories above)
00014  */
00015 #ifndef __L4SYS__INCLUDE__ARCH_ARM_MEM_OP_H__
00016 #define __L4SYS__INCLUDE__ARCH_ARM_MEM_OP_H__
00017
00018 #include <l4/sys/compiler.h>
00019 #include <l4/sys/syscall_defs.h>
00020
00021 L4_BEGIN_DECLS
00022
00035
00040 enum L4_mem_op_widths
00041 {
00042     L4_MEM_WIDTH_1BYTE = 0,
00043     L4_MEM_WIDTH_2BYTE = 1,
00044     L4_MEM_WIDTH_4BYTE = 2,
00045 };
00046
00059 L4_INLINE unsigned long
00060 l4_mem_read(unsigned long virtaddress, unsigned width);
00061
00074 L4_INLINE void
00075 l4_mem_write(unsigned long virtaddress, unsigned width,
00076              unsigned long value);
00077
00078 enum L4_mem_ops
00079 {
00080     L4_MEM_OP_MEM_READ = 0x10,
00081     L4_MEM_OP_MEM_WRITE = 0x11,
00082 };
00083
00087 L4_INLINE unsigned long

```

```


00088 l4_mem_arm_op_call(unsigned long op,
00089                    unsigned long va,
00090                    unsigned long width,
00091                    unsigned long value);
00092
00093
00094
00095 L4_INLINE unsigned long
00096 l4_mem_arm_op_call(unsigned long op,
00097                    unsigned long va,
00098                    unsigned long width,
00099                    unsigned long value)
00100 {
00101     register unsigned long _op    __asm__ ("r0") = op;
00102     register unsigned long _va    __asm__ ("r1") = va;
00103     register unsigned long _width __asm__ ("r2") = width;
00104     register unsigned long _value __asm__ ("r3") = value;
00105
00106     __asm__ __volatile__
00107     ("@ l4_cache_op_arm_call(start) \n\t"
00108      "mov     r5, %[sc]          \n\t"
00109      "blx     __l4_sys_syscall   \n\t"
00110      "@ l4_cache_op_arm_call(end) \n\t"
00111      :
00112      "=r" (_op),
00113      "=r" (_va),
00114      "=r" (_width),
00115      "=r" (_value)
00116      :
00117      [sc] "i" (L4_SYSCALL_MEM_OP),
00118      "0" (_op),
00119      "1" (_va),
00120      "2" (_width),
00121      "3" (_value)
00122      :
00123      "cc", "memory", "r5", "ip", "lr"
00124      );
00125
00126     return _value;
00127 }
00128
00129 L4_INLINE unsigned long
00130 l4_mem_read(unsigned long virtaddress, unsigned width)
00131 {
00132     return l4_mem_arm_op_call(L4_MEM_OP_MEM_READ, virtaddress, width, 0);
00133 }
00134
00135 L4_INLINE void
00136 l4_mem_write(unsigned long virtaddress, unsigned width,
00137              unsigned long value)
00138 {
00139     l4_mem_arm_op_call(L4_MEM_OP_MEM_WRITE, virtaddress, width, value);
00140 }
00141
00142 L4_END_DECLS
00143
00144 #endif /* ! __L4SYS__INCLUDE__ARCH_ARM__MEM_OP_H__ */

```

## 16.115 arm/l4/sys/syscall\_defs.h File Reference

Syscall entry definitions.

This graph shows which files directly or indirectly include this file:



### 16.115.1 Detailed Description

Syscall entry definitions.

Definition in file [syscall\\_defs.h](#).

## 16.116 syscall\_defs.h

[Go to the documentation of this file.](#)

```
00001
00005 /*
00006  * (c) 2010 Adam Lackorzynski <adam@os.inf.tu-dresden.de>
00007  *      economic rights: Technische Universität Dresden (Germany)
00008  *
00009  * License: see LICENSE.spdx (in this directory or the directories above)
00010  */
00011 #ifndef __L4SYS__ARCH_ARM__L4API_L4F__SYSCALL_DEFS_H__
00012 #define __L4SYS__ARCH_ARM__L4API_L4F__SYSCALL_DEFS_H__
00013
00014 #define L4_SYSCALL_INVOKE      (0)
00015 #define L4_SYSCALL_MEM_OP      (1)
00016
00017 #endif /* __L4SYS__ARCH_ARM__L4API_L4F__SYSCALL_DEFS_H__ */
```

## 16.117 vm.h


```
00001
00006 /*
00007  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>
00008  *      economic rights: Technische Universität Dresden (Germany)
00009  *
00010  * License: see LICENSE.spdx (in this directory or the directories above)
00011  */
00012 #pragma once
00013
00014 #include <l4/sys/__vm-svm.h>
00015 #include <l4/sys/__vm-vmx.h>
```

## 16.118 arm/l4/sys/vm.h File Reference

ARM virtualization interface.

```
#include <l4/sys/err.h>
#include <l4/sys/types.h>
```

Include dependency graph for vm.h:



## Data Structures

- struct [l4\\_vm\\_tz\\_state](#)  
*state structure for TrustZone VMs*

## 16.118.1 Detailed Description

ARM virtualization interface.

Definition in file [vm.h](#).

## 16.119 vm.h

[Go to the documentation of this file.](#)

```

00001
00005 /*
00006  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00007  *          Torsten Frenzel <frenzel@os.inf.tu-dresden.de>
00008  *          economic rights: Technische Universität Dresden (Germany)
00009  *
00010  * License: see LICENSE.spdx (in this directory or the directories above)
00011  */
00012 #pragma once
00013
00014 #include <l4/sys/err.h>
00015 #include <l4/sys/types.h>
00016
00022
00027 struct l4_vm_tz_state_mode
00028 {
00029     l4_umword_t sp;
00030     l4_umword_t lr;
00031     l4_umword_t spsr;
00032 };
00033

```

```

00034 struct l4_vm_tz_state_irq_inject
00035 {
00036     l4_uint32_t group;
00037     l4_uint32_t irqs[8];
00038 };
00039
00044 struct l4_vm_tz_state
00045 {
00046     l4_umword_t r[13]; // r0 - r12
00047
00048     l4_umword_t sp_usr;
00049     l4_umword_t lr_usr;
00050
00051     struct l4_vm_tz_state_mode irq;
00052
00053     l4_umword_t r_fiq[5]; // r8 - r12
00054     struct l4_vm_tz_state_mode fiq;
00055     struct l4_vm_tz_state_mode abt;
00056     struct l4_vm_tz_state_mode und;
00057     struct l4_vm_tz_state_mode svc;
00058
00059     l4_umword_t pc;
00060     l4_umword_t cpsr;
00061
00062     l4_umword_t pending_events;
00063     l4_uint32_t cpacr;
00064     l4_umword_t cp10_fpexc;
00065
00066     l4_umword_t pfs;
00067     l4_umword_t pfa;
00068     l4_umword_t exit_reason;
00069
00070     struct l4_vm_tz_state_irq_inject irq_inject;
00071 };
00072
00073 enum L4_vm_exit_reason
00074 {
00075     L4_vm_exit_reason_vmm_call    = 1,
00076     L4_vm_exit_reason_inst_abort = 2,
00077     L4_vm_exit_reason_data_abort = 3,
00078     L4_vm_exit_reason_irq        = 4,
00079     L4_vm_exit_reason_fiq        = 5,
00080     L4_vm_exit_reason_undef      = 6,
00081 };
00082
00083 L4_INLINE int
00084 l4_vm_tz_irq_inject(struct l4_vm_tz_state *state, unsigned irq);
00085
00086 L4_INLINE int
00087 l4_vm_tz_irq_inject(struct l4_vm_tz_state *state, unsigned irq)
00088 {
00089     if (irq > sizeof(state->irq_inject.irqs) * 8)
00090         return -L4_EINVAL;
00091
00092     unsigned g = irq / 32;
00093     state->irq_inject.group |= 1 << g;
00094     state->irq_inject.irqs[g] |= 1 << (irq & 31);
00095
00096     return 0;
00097 }

```

## 16.120 vm.h

```

00001
00002

```

## 16.121 vm.h

```

00001
00006 /*
00007  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00008  *      Henning Schild <hschild@os.inf.tu-dresden.de>
00009  *      economic rights: Technische Universität Dresden (Germany)
00010  *
00011  * License: see LICENSE.spdx (in this directory or the directories above)
00012  */
00013 #pragma once
00014
00015 #include <l4/sys/__vm-svm.h>
00016 #include <l4/sys/__vm-vmx.h>

```

## 16.122 amd64/l4/util/arch/l4\_macros.h File Reference

Main function.

### 16.122.1 Detailed Description

Main function.

Date

08/29/2000

Author

Frank Mehnert [fm3@os.inf.tu-dresden.de](mailto:fm3@os.inf.tu-dresden.de)

Definition in file [l4\\_macros.h](#).

## 16.123 l4\_macros.h

[Go to the documentation of this file.](#)

```
00001
00007
00008 /*
00009  * (c) 2006-2009 Author(s)
00010  *     economic rights: Technische Universität Dresden (Germany)
00011  * License: see LICENSE.spdx (in this directory or the directories above)
00012  */
00013
00014 #ifndef _L4UTIL__ARCH_AMD64__L4_MACROS_H
00015 #define _L4UTIL__ARCH_AMD64__L4_MACROS_H
00016
00017 #ifndef l4_addr_fmt
00018 # define l4_addr_fmt    "%016lx"
00019 #endif
00020
00021 #endif /* !_L4UTIL__ARCH_AMD64__L4_MACROS_H */
```

## 16.124 arm/l4/util/arch/l4\_macros.h File Reference

Main function.

### 16.124.1 Detailed Description

Main function.

Date

08/29/2000

Author

Frank Mehnert [fm3@os.inf.tu-dresden.de](mailto:fm3@os.inf.tu-dresden.de)

Definition in file [l4\\_macros.h](#).

## 16.125 l4\_macros.h

[Go to the documentation of this file.](#)


```
00001
00007
00008 /*
00009  * (c) 2006-2009 Author(s)
00010  *     economic rights: Technische Universität Dresden (Germany)
00011  * License: see LICENSE.spdx (in this directory or the directories above)
00012  */
00013
00014 #ifndef _L4UTIL__ARCH_ARM__L4_MACROS_H
00015 #define _L4UTIL__ARCH_ARM__L4_MACROS_H
00016
00017 #ifndef l4_addr_fmt
00018 #   define l4_addr_fmt    "%08lx"
00019 #endif
00020
00021 #endif /* !_L4UTIL__ARCH_ARM__L4_MACROS_H */
```

## 16.126 l4/util/l4\_macros.h File Reference

Some useful generic macros, L4f version.

```
#include <l4/util/arch/l4_macros.h>
```

Include dependency graph for l4\_macros.h:



### 16.126.1 Detailed Description

Some useful generic macros, L4f version.

Date

11/12/2002

Author

Lars Reuther [reuther@os.inf.tu-dresden.de](mailto:reuther@os.inf.tu-dresden.de)

Definition in file [l4\\_macros.h](#).



## 16.127 l4\_macros.h

[Go to the documentation of this file.](#)

```
00001 /*****
00008 */
00009 * (c) 2000-2009 Author(s)
00010 *     economic rights: Technische Universität Dresden (Germany)
00011 * License: see LICENSE.spdx (in this directory or the directories above)
00012 */
00013
00014 /*****
00015
00016 #pragma once
00017
00018 #include <l4/util/arch/l4_macros.h>
00019
00020 /*****
00021 *** generic macros
00022 *****/
00023
00024 /* generate L4 thread id printf string */
00025 #ifndef l4util_idstr
00026 #   define l4util_idfmt          "%lx"
00027 #   define l4util_idfmt_adjust  "%04lx"
00028 #   define l4util_idstr(tid)    (tid » L4_CAP_SHIFT)
00029 #endif
00030
```

## 16.128 x86/l4/util/arch/l4\_macros.h File Reference

Main function.

### 16.128.1 Detailed Description

Main function.

#### Date

08/29/2000

#### Author

Frank Mehnert [fm3@os.inf.tu-dresden.de](mailto:fm3@os.inf.tu-dresden.de)

Definition in file [l4\\_macros.h](#).

## 16.129 l4\_macros.h

[Go to the documentation of this file.](#)

```
00001
00007
00008 /*
00009 * (c) 2006-2009 Author(s)
00010 *     economic rights: Technische Universität Dresden (Germany)
00011 * License: see LICENSE.spdx (in this directory or the directories above)
00012 */
00013
00014
00015 #ifndef _L4UTIL__ARCH_X86__L4_MACROS_H
00016 #define _L4UTIL__ARCH_X86__L4_MACROS_H
00017
00018 #ifndef l4_addr_fmt
00019 #   define l4_addr_fmt          "%08lx"
00020 #endif
00021
00022 #endif /* !_L4UTIL__ARCH_X86__L4_MACROS_H */
```

## 16.130 thread.h

```
00001 /*
00002  * Copyright (C) 2026 Kernkonzept GmbH.
00003  * Author(s): Jan Klötzke <jan.kloetzke@kernkonzept.com>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007 #pragma once
```

## 16.131 thread.h

```
00001 /*
00002  * Copyright (C) 2026 Kernkonzept GmbH.
00003  * Author(s): Jan Klötzke <jan.kloetzke@kernkonzept.com>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007 #pragma once
```

## 16.132 arm/l4/sys/arch/thread.h File Reference

ARM-specific thread related definitions.

### Enumerations

- enum [L4\\_thread\\_ex\\_regs\\_flags\\_arm](#) { [L4\\_THREAD\\_EX\\_REGS\\_ARM\\_SET\\_EL\\_MASK](#) = 0x3 << 24 , [L4\\_THREAD\\_EX\\_REGS\\_ARM\\_SET\\_EL\\_KEEP](#) = 0x0 << 24 , [L4\\_THREAD\\_EX\\_REGS\\_ARM\\_SET\\_EL\\_EL0](#) = 0x1 << 24 , [L4\\_THREAD\\_EX\\_REGS\\_ARM\\_SET\\_EL\\_EL1](#) = 0x2 << 24 }
- Arm specific [L4::Thread::ex\\_regs\(\)](#) flags.*

### Functions

- [l4\\_msgtag\\_t](#) [l4\\_thread\\_arm\\_set\\_tpidruro](#) ([l4\\_cap\\_idx\\_t](#) thread, [l4\\_addr\\_t](#) tpidruro) [L4\\_NOTHROW](#)
- Set the [TPIDRURO](#) thread specific register.*

### 16.132.1 Detailed Description

ARM-specific thread related definitions.

Definition in file [thread.h](#).

## 16.133 thread.h

[Go to the documentation of this file.](#)

```

00001
00005 /*
00006  * (c) 2013 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00007  *      economic rights: Technische Universität Dresden (Germany)
00008  *
00009  * License: see LICENSE.spdx (in this directory or the directories above)
00010  */
00011 #pragma once
00012
00013 // Use the full documentation from ARM64. Otherwise \parameters and \return
00014 // would occur twice in the Doxygen documentation of this function.
00018 L4_INLINE l4_msgtag_t
00019 l4_thread_arm_set_tpidruro(l4_cap_idx_t thread, l4_addr_t tpidruro) L4_NOTHROW;
00020
00025 L4_INLINE l4_msgtag_t
00026 l4_thread_arm_set_tpidruro_u(l4_cap_idx_t thread, l4_addr_t tpidruro,
00027                             l4_utcb_t *utcb) L4_NOTHROW;
00028
00037 enum l4_thread_ex_regs_flags_arm
00038 {
00040     L4_THREAD_EX_REGS_ARM_SET_EL_MASK      = 0x3 << 24,
00042     L4_THREAD_EX_REGS_ARM_SET_EL_KEEP      = 0x0 << 24,
00044     L4_THREAD_EX_REGS_ARM_SET_EL_EL0       = 0x1 << 24,
00046     L4_THREAD_EX_REGS_ARM_SET_EL_EL1       = 0x2 << 24,
00047 };
00048
00049 /* IMPLEMENTATION -----*/
00050
00051 L4_INLINE l4_msgtag_t
00052 l4_thread_arm_set_tpidruro_u(l4_cap_idx_t thread, l4_addr_t tpidruro,
00053                             l4_utcb_t *utcb) L4_NOTHROW
00054 {
00055     l4_msg_regs_t *v = l4_utcb_mr_u(utcb);
00056     v->mr[0] = L4_THREAD_ARM_TPIDRURO_OP;
00057     v->mr[1] = tpidruro;
00058     return l4_ipc_call(thread, utcb, l4_msgtag(L4_PROTO_THREAD, 2, 0, 0),
00059                      L4_IPC_NEVER);
00060 }
00061
00062 L4_INLINE l4_msgtag_t
00063 l4_thread_arm_set_tpidruro(l4_cap_idx_t thread, l4_addr_t tpidruro) L4_NOTHROW
00064 {
00065     return l4_thread_arm_set_tpidruro_u(thread, tpidruro, l4_utcb());
00066 }

```

## 16.134 thread.h

```

00001 /*
00002  * Copyright (C) 2026 Kernkonzept GmbH.
00003  * Author(s): Jan Klötzke <jan.kloetzke@kernkonzept.com>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007 #pragma once

```

## 16.135 arm64/l4/sys/arch/thread.h File Reference

ARM64-specific thread related definitions.

### Enumerations

- enum [L4\\_thread\\_ex\\_regs\\_flags\\_arm64](#) { [L4\\_THREAD\\_EX\\_REGS\\_ARM64\\_SET\\_EL\\_MASK](#) = 0x3 << 24 , [L4\\_THREAD\\_EX\\_REGS\\_ARM64\\_SET\\_EL\\_KEEP](#) = 0x0 << 24 , [L4\\_THREAD\\_EX\\_REGS\\_ARM64\\_SET\\_EL\\_EL0](#) = 0x1 << 24 , [L4\\_THREAD\\_EX\\_REGS\\_ARM64\\_SET\\_EL\\_EL1](#) = 0x2 << 24 }
- Arm64 specific [L4::Thread::ex\\_regs\(\)](#) flags.*

## Functions

- [l4\\_msgtag\\_t l4\\_thread\\_arm\\_set\\_tpidruro](#) ([l4\\_cap\\_idx\\_t](#) thread, [l4\\_addr\\_t](#) tpidruro) [L4\\_NOTHROW](#)  
*Set the TPIDRURO thread specific register.*

### 16.135.1 Detailed Description

ARM64-specific thread related definitions.

Definition in file [thread.h](#).

## 16.136 thread.h

[Go to the documentation of this file.](#)

```

00001
00005 /*
00006  * (c) 2013 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00007  *      economic rights: Technische Universität Dresden (Germany)
00008  *
00009  * License: see LICENSE.spdx (in this directory or the directories above)
00010  */
00011 #pragma once
00012
00025 L4_INLINE l4_msgtag_t
00026 l4_thread_arm_set_tpidruro(l4_cap_idx_t thread, l4_addr_t tpidruro) L4_NOTHROW;
00027
00032 L4_INLINE l4_msgtag_t
00033 l4_thread_arm_set_tpidruro_u(l4_cap_idx_t thread, l4_addr_t tpidruro,
00034                             l4_utcb_t *utcb) L4_NOTHROW;
00035
00044 enum L4_thread_ex_regs_flags_arm64
00045 {
00047     L4_THREAD_EX_REGS_ARM64_SET_EL_MASK      = 0x3 << 24,
00049     L4_THREAD_EX_REGS_ARM64_SET_EL_KEEP      = 0x0 << 24,
00051     L4_THREAD_EX_REGS_ARM64_SET_EL_EL0       = 0x1 << 24,
00053     L4_THREAD_EX_REGS_ARM64_SET_EL_EL1       = 0x2 << 24,
00054 };
00055
00056 /* IMPLEMENTATION -----*/
00057
00058 L4_INLINE l4_msgtag_t
00059 l4_thread_arm_set_tpidruro_u(l4_cap_idx_t thread, l4_addr_t tpidruro,
00060                             l4_utcb_t *utcb) L4_NOTHROW
00061 {
00062     l4_msg_regs_t *v = l4_utcb_mr_u(utcb);
00063     v->mr[0] = L4_THREAD_ARM_TPIDRURO_OP;
00064     v->mr[1] = tpidruro;
00065     return l4_ipc_call(thread, utcb, l4_msgtag(L4_PROTO_THREAD, 2, 0, 0),
00066                       L4_IPC_NEVER);
00067 }
00068
00069 L4_INLINE l4_msgtag_t
00070 l4_thread_arm_set_tpidruro(l4_cap_idx_t thread, l4_addr_t tpidruro) L4_NOTHROW
00071 {
00072     return l4_thread_arm_set_tpidruro_u(thread, tpidruro, l4_utcb());
00073 }

```

## 16.137 l4/sys/thread.h File Reference


Common thread related definitions.

```


#include <l4/sys/types.h>
#include <l4/sys/utcb.h>
#include <l4/sys/ipc.h>

```

```
#include <linux/sys/arch/thread.h>
```



This graph shows which files directly or indirectly include this file:



## Enumerations

- enum `L4_thread_ops` {  
`L4_THREAD_CONTROL_OP` = 0UL , `L4_THREAD_EX_REGS_OP` = 1UL , `L4_THREAD_SWITCH_OP` = 2UL , `L4_THREAD_STATS_OP` = 3UL ,  
`L4_THREAD_VCPU_RESUME_OP` = 4UL , `L4_THREAD_REGISTER_DELETE_IRQ_OP` = 5UL ,  
`L4_THREAD_MODIFY_SENDER_OP` = 6UL , `L4_THREAD_VCPU_CONTROL_OP` = 7UL ,  
`L4_THREAD_VCPU_CONTROL_EXT_OP` = `L4_THREAD_VCPU_CONTROL_OP` | 0x10000 , `L4_THREAD_REGISTER_DO`  
= 8UL , `L4_THREAD_X86_GDT_OP` = 0x10UL , `L4_THREAD_ARM_TPIDRURO_OP` = 0x10UL ,  
`L4_THREAD_AMD64_SET_SEGMENT_BASE_OP` = 0x12UL , `L4_THREAD_AMD64_GET_SEGMENT_INFO_OP`  
= 0x13UL , `L4_THREAD_OPCODE_MASK` = 0xffff }
- Operations on thread objects.*
- enum `L4_thread_control_flags` { `L4_THREAD_CONTROL_SET_PAGER` = 0x0010000 , `L4_THREAD_CONTROL_BIND_TASK`  
= 0x0200000 , `L4_THREAD_CONTROL_ALIEN` = 0x0400000 , `L4_THREAD_CONTROL_SET_EXC_HANDLER`  
= 0x1000000 }
- Flags for the thread control operation.*

- enum `L4_thread_control_mr_indices` {  
`L4_THREAD_CONTROL_MR_IDX_FLAGS` = 0 , `L4_THREAD_CONTROL_MR_IDX_PAGER` = 1 ,  
`L4_THREAD_CONTROL_MR_IDX_EXC_HANDLER` = 2 , `L4_THREAD_CONTROL_MR_IDX_FLAG_VALS`  
= 4 ,  
`L4_THREAD_CONTROL_MR_IDX_BIND_UTCB` = 5 , `L4_THREAD_CONTROL_MR_IDX_BIND_TASK` = 6  
}

*Indices for the values in the message register for thread control.*

- enum `L4_thread_ex_regs_flags` { `L4_THREAD_EX_REGS_CANCEL` = 0x10000UL , `L4_THREAD_EX_REGS_TRIGGER_EXC`  
= 0x20000UL , `L4_THREAD_EX_REGS_ARCH_MASK` = 0xff000000UL }

*Flags for the thread ex-regs operation.*

## Functions

- `l4_msgtag_t l4_thread_ex_regs` (`l4_cap_idx_t` thread, `l4_addr_t` ip, `l4_addr_t` sp, `l4_umword_t` flags)  
`L4_NOTHROW`  
*Exchange basic thread registers.*
- `l4_msgtag_t l4_thread_ex_regs_u` (`l4_cap_idx_t` thread, `l4_addr_t` ip, `l4_addr_t` sp, `l4_umword_t` flags,  
`l4_utcb_t` \*utcb) `L4_NOTHROW`  
*Exchange basic thread registers.*
- `l4_msgtag_t l4_thread_ex_regs_ret` (`l4_cap_idx_t` thread, `l4_addr_t` \*ip, `l4_addr_t` \*sp, `l4_umword_t` \*flags)  
`L4_NOTHROW`  
*Exchange basic thread registers and return previous values.*
- `l4_msgtag_t l4_thread_ex_regs_ret_u` (`l4_cap_idx_t` thread, `l4_addr_t` \*ip, `l4_addr_t` \*sp, `l4_umword_t`  
\*flags, `l4_utcb_t` \*utcb) `L4_NOTHROW`  
*Exchange basic thread registers and return previous values.*
- void `l4_thread_control_start` (void) `L4_NOTHROW`  
*Start a thread control API sequence.*
- void `l4_thread_control_pager` (`l4_cap_idx_t` pager) `L4_NOTHROW`  
*Set the pager.*
- void `l4_thread_control_exc_handler` (`l4_cap_idx_t` exc\_handler) `L4_NOTHROW`  
*Set the exception handler.*
- void `l4_thread_control_bind` (`l4_utcb_t` \*thread\_utcb, `l4_cap_idx_t` task) `L4_NOTHROW`  
*Bind the thread to a task.*
- void `l4_thread_control_alien` (int on) `L4_NOTHROW`  
*Enable alien mode.*
- `l4_msgtag_t l4_thread_control_commit` (`l4_cap_idx_t` thread) `L4_NOTHROW`  
*Commit the thread control parameters.*
- `l4_msgtag_t l4_thread_yield` (void) `L4_NOTHROW`  
*Yield current time slice.*
- `l4_msgtag_t l4_thread_switch` (`l4_cap_idx_t` to\_thread) `L4_NOTHROW`  
*Switch to another thread (and donate the remaining time slice).*
- `l4_msgtag_t l4_thread_stats_time` (`l4_cap_idx_t` thread, `l4_kernel_clock_t` \*us) `L4_NOTHROW`  
*Get consumed time of thread in  $\mu$ s.*
- `l4_msgtag_t l4_thread_vcpu_resume_start` (void) `L4_NOTHROW`  
*vCPU return from event handler.*
- `l4_msgtag_t l4_thread_vcpu_resume_commit` (`l4_cap_idx_t` thread, `l4_msgtag_t` tag) `L4_NOTHROW`  
*Commit vCPU resume.*
- `l4_msgtag_t l4_thread_vcpu_control` (`l4_cap_idx_t` thread, `l4_addr_t` vcpu\_state) `L4_NOTHROW`  
*Enable the vCPU feature for the thread.*
- `l4_msgtag_t l4_thread_vcpu_control_u` (`l4_cap_idx_t` thread, `l4_addr_t` vcpu\_state, `l4_utcb_t` \*utcb)  
`L4_NOTHROW`

- Enable the vCPU feature for the thread.*
- [l4\\_msgtag\\_t l4\\_thread\\_vcpu\\_control\\_ext](#) ([l4\\_cap\\_idx\\_t](#) thread, [l4\\_addr\\_t](#) ext\_vcpu\_state) [L4\\_NOTHROW](#)
- Enable the extended vCPU feature for the thread.*
- [l4\\_msgtag\\_t l4\\_thread\\_vcpu\\_control\\_ext\\_u](#) ([l4\\_cap\\_idx\\_t](#) thread, [l4\\_addr\\_t](#) ext\_vcpu\_state, [l4\\_utcb\\_t](#) \*utcb) [L4\\_NOTHROW](#)
- Enable the extended vCPU feature for the thread.*
- [l4\\_msgtag\\_t l4\\_thread\\_register\\_del\\_irq](#) ([l4\\_cap\\_idx\\_t](#) thread, [l4\\_cap\\_idx\\_t](#) irq) [L4\\_NOTHROW](#)
- Register an IRQ that will trigger upon deletion events.*
- [l4\\_msgtag\\_t l4\\_thread\\_modify\\_sender\\_start](#) (void) [L4\\_NOTHROW](#)
- Start a thread sender modification sequence.*
- [int l4\\_thread\\_modify\\_sender\\_add](#) ([l4\\_umword\\_t](#) match\_mask, [l4\\_umword\\_t](#) match, [l4\\_umword\\_t](#) del\_bits, [l4\\_umword\\_t](#) add\_bits, [l4\\_msgtag\\_t](#) \*tag) [L4\\_NOTHROW](#)
- Add a modification pattern to a sender modification sequence.*
- [l4\\_msgtag\\_t l4\\_thread\\_modify\\_sender\\_commit](#) ([l4\\_cap\\_idx\\_t](#) thread, [l4\\_msgtag\\_t](#) tag) [L4\\_NOTHROW](#)
- Apply (commit) a sender modification sequence.*
- [l4\\_msgtag\\_t l4\\_thread\\_register\\_doorbell\\_irq](#) ([l4\\_cap\\_idx\\_t](#) thread, [l4\\_cap\\_idx\\_t](#) irq) [L4\\_NOTHROW](#)
- Register an IRQ that will trigger when a forwarded virtual interrupt is pending.*

### 16.137.1 Detailed Description

Common thread related definitions.

Definition in file [thread.h](#).

## 16.138 thread.h

[Go to the documentation of this file.](#)

```

00001
00005 /*
00006  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00007  *      Alexander Warg <warg@os.inf.tu-dresden.de>,
00008  *      Björn Döbel <doebel@os.inf.tu-dresden.de>,
00009  *      Torsten Frenzel <frenzel@os.inf.tu-dresden.de>
00010  *      economic rights: Technische Universität Dresden (Germany)
00011  *
00012  * License: see LICENSE.spdx (in this directory or the directories above)
00013  */
00014 #pragma once
00015
00016 #include <l4/sys/types.h>
00017 #include <l4/sys/utcb.h>
00018 #include <l4/sys/ipc.h>
00019
00054
00055
00083 L4_INLINE l4_msgtag_t
00084 l4_thread_ex_regs(l4_cap_idx_t thread, l4_addr_t ip, l4_addr_t sp,
00085                  l4_umword_t flags) L4_NOTHROW;
00086
00093 L4_INLINE l4_msgtag_t
00094 l4_thread_ex_regs_u(l4_cap_idx_t thread, l4_addr_t ip, l4_addr_t sp,
00095                    l4_umword_t flags, l4_utcb_t *utcb) L4_NOTHROW;
00096
00129 L4_INLINE l4_msgtag_t
00130 l4_thread_ex_regs_ret(l4_cap_idx_t thread, l4_addr_t *ip, l4_addr_t *sp,
00131                      l4_umword_t *flags) L4_NOTHROW;
00132
00139 L4_INLINE l4_msgtag_t
00140 l4_thread_ex_regs_ret_u(l4_cap_idx_t thread, l4_addr_t *ip, l4_addr_t *sp,
00141                         l4_umword_t *flags, l4_utcb_t *utcb) L4_NOTHROW;
00142
00143
00144
00170

```

```

00190 L4_INLINE void
00191 l4_thread_control_start(void) L4_NOTHROW;
00192
00197 L4_INLINE void
00198 l4_thread_control_start_u(l4_utcb_t *utcb) L4_NOTHROW;
00199
00209 L4_INLINE void
00210 l4_thread_control_pager(l4_cap_idx_t pager) L4_NOTHROW;
00211
00216 L4_INLINE void
00217 l4_thread_control_pager_u(l4_cap_idx_t pager, l4_utcb_t *utcb) L4_NOTHROW;
00218
00228 L4_INLINE void
00229 l4_thread_control_exc_handler(l4_cap_idx_t exc_handler) L4_NOTHROW;
00230
00235 L4_INLINE void
00236 l4_thread_control_exc_handler_u(l4_cap_idx_t exc_handler,
00237                                l4_utcb_t *utcb) L4_NOTHROW;
00238
00266 L4_INLINE void
00267 l4_thread_control_bind(l4_utcb_t *thread_utcb,
00268                        l4_cap_idx_t task) L4_NOTHROW;
00269
00274 L4_INLINE void
00275 l4_thread_control_bind_u(l4_utcb_t *thread_utcb,
00276                          l4_cap_idx_t task, l4_utcb_t *utcb) L4_NOTHROW;
00277
00301 L4_INLINE void
00302 l4_thread_control_alien(int on) L4_NOTHROW;
00303
00308 L4_INLINE void
00309 l4_thread_control_alien_u(l4_utcb_t *utcb, int on) L4_NOTHROW;
00310
00311
00312
00313
00330 L4_INLINE l4_msgtag_t
00331 l4_thread_control_commit(l4_cap_idx_t thread) L4_NOTHROW;
00332
00337 L4_INLINE l4_msgtag_t
00338 l4_thread_control_commit_u(l4_cap_idx_t thread, l4_utcb_t *utcb) L4_NOTHROW;
00339
00346 L4_INLINE l4_msgtag_t
00347 l4_thread_yield(void) L4_NOTHROW;
00348
00357 L4_INLINE l4_msgtag_t
00358 l4_thread_switch(l4_cap_idx_t to_thread) L4_NOTHROW;
00359
00364 L4_INLINE l4_msgtag_t
00365 l4_thread_switch_u(l4_cap_idx_t to_thread, l4_utcb_t *utcb) L4_NOTHROW;
00366
00367
00368
00378 L4_INLINE l4_msgtag_t
00379 l4_thread_stats_time(l4_cap_idx_t thread, l4_kernel_clock_t *us) L4_NOTHROW;
00380
00385 L4_INLINE l4_msgtag_t
00386 l4_thread_stats_time_u(l4_cap_idx_t thread, l4_kernel_clock_t *us,
00387                        l4_utcb_t *utcb) L4_NOTHROW;
00388
00389
00400 L4_INLINE l4_msgtag_t
00401 l4_thread_vcpu_resume_start(void) L4_NOTHROW;
00402
00407 L4_INLINE l4_msgtag_t
00408 l4_thread_vcpu_resume_start_u(l4_utcb_t *utcb) L4_NOTHROW;
00409
00457 L4_INLINE l4_msgtag_t
00458 l4_thread_vcpu_resume_commit(l4_cap_idx_t thread,
00459                               l4_msgtag_t tag) L4_NOTHROW;
00460
00465 L4_INLINE l4_msgtag_t
00466 l4_thread_vcpu_resume_commit_u(l4_cap_idx_t thread,
00467                                 l4_msgtag_t tag, l4_utcb_t *utcb) L4_NOTHROW;
00468
00469
00489 L4_INLINE l4_msgtag_t
00490 l4_thread_vcpu_control(l4_cap_idx_t thread, l4_addr_t vcpu_state) L4_NOTHROW;
00491
00499 L4_INLINE l4_msgtag_t
00500 l4_thread_vcpu_control_u(l4_cap_idx_t thread, l4_addr_t vcpu_state,
00501                           l4_utcb_t *utcb) L4_NOTHROW;
00502
00534 L4_INLINE l4_msgtag_t
00535 l4_thread_vcpu_control_ext(l4_cap_idx_t thread, l4_addr_t ext_vcpu_state) L4_NOTHROW;
00536
00544 L4_INLINE l4_msgtag_t

```



```

00545 l4_thread_vcpu_control_ext_u(l4_cap_idx_t thread, l4_addr_t ext_vcpu_state,
00546                               l4_utcb_t *utcb) L4_NOTHROW;
00547
00548
00572 L4_INLINE l4_msgtag_t
00573 l4_thread_register_del_irq(l4_cap_idx_t thread, l4_cap_idx_t irq) L4_NOTHROW;
00574
00579 L4_INLINE l4_msgtag_t
00580 l4_thread_register_del_irq_u(l4_cap_idx_t thread, l4_cap_idx_t irq,
00581                              l4_utcb_t *utcb) L4_NOTHROW;
00582
00604 L4_INLINE l4_msgtag_t
00605 l4_thread_modify_sender_start(void) L4_NOTHROW;
00606
00611 L4_INLINE l4_msgtag_t
00612 l4_thread_modify_sender_start_u(l4_utcb_t *u) L4_NOTHROW;
00613
00638 L4_INLINE int
00639 l4_thread_modify_sender_add(l4_umword_t match_mask,
00640                             l4_umword_t match,
00641                             l4_umword_t del_bits,
00642                             l4_umword_t add_bits,
00643                             l4_msgtag_t *tag) L4_NOTHROW;
00644
00649 L4_INLINE int
00650 l4_thread_modify_sender_add_u(l4_umword_t match_mask,
00651                               l4_umword_t match,
00652                               l4_umword_t del_bits,
00653                               l4_umword_t add_bits,
00654                               l4_msgtag_t *tag, l4_utcb_t *u) L4_NOTHROW;
00655
00681 L4_INLINE l4_msgtag_t
00682 l4_thread_modify_sender_commit(l4_cap_idx_t thread, l4_msgtag_t tag) L4_NOTHROW;
00683
00688 L4_INLINE l4_msgtag_t
00689 l4_thread_modify_sender_commit_u(l4_cap_idx_t thread, l4_msgtag_t tag,
00690                                  l4_utcb_t *u) L4_NOTHROW;
00691
00692
00713 L4_INLINE l4_msgtag_t
00714 l4_thread_register_doorbell_irq(l4_cap_idx_t thread,
00715                                 l4_cap_idx_t irq) L4_NOTHROW;
00716
00721 L4_INLINE l4_msgtag_t
00722 l4_thread_register_doorbell_irq_u(l4_cap_idx_t thread, l4_cap_idx_t irq,
00723                                   l4_utcb_t *u) L4_NOTHROW;
00724
00725
00732 enum L4_thread_ops
00733 {
00734     L4_THREAD_CONTROL_OP           = 0UL,
00735     L4_THREAD_EX_REGS_OP          = 1UL,
00736     L4_THREAD_SWITCH_OP           = 2UL,
00737     L4_THREAD_STATS_OP            = 3UL,
00738     L4_THREAD_VCPU_RESUME_OP       = 4UL,
00739     L4_THREAD_REGISTER_DELETE_IRQ_OP = 5UL,
00740     L4_THREAD_MODIFY_SENDER_OP     = 6UL,
00741     L4_THREAD_VCPU_CONTROL_OP      = 7UL,
00742     L4_THREAD_VCPU_CONTROL_EXT_OP  = L4_THREAD_VCPU_CONTROL_OP | 0x10000,
00743     L4_THREAD_REGISTER_DOORBELL_IRQ_OP = 8UL,
00744     L4_THREAD_X86_GDT_OP           = 0x10UL,
00745     L4_THREAD_ARM_TPIDRURO_OP      = 0x10UL,
00746     L4_THREAD_AMD64_SET_SEGMENT_BASE_OP = 0x12UL,
00747     L4_THREAD_AMD64_GET_SEGMENT_INFO_OP = 0x13UL,
00748     L4_THREAD_OPCODE_MASK         = 0xffff,
00749 };
00750
00761 enum L4_thread_control_flags
00762 {
00764     L4_THREAD_CONTROL_SET_PAGER      = 0x0010000,
00766     L4_THREAD_CONTROL_BIND_TASK     = 0x0200000,
00768     L4_THREAD_CONTROL_ALIEN         = 0x0400000,
00770     L4_THREAD_CONTROL_SET_EXC_HANDLER = 0x1000000,
00771 };
00772
00782 enum L4_thread_control_mr_indices
00783 {
00784     L4_THREAD_CONTROL_MR_IDX_FLAGS    = 0,
00785     L4_THREAD_CONTROL_MR_IDX_PAGER    = 1,
00786     L4_THREAD_CONTROL_MR_IDX_EXC_HANDLER = 2,
00787     L4_THREAD_CONTROL_MR_IDX_FLAG_VALS = 4,
00788     L4_THREAD_CONTROL_MR_IDX_BIND_UTCB = 5,
00789     L4_THREAD_CONTROL_MR_IDX_BIND_TASK = 6,
00790 };
00791
00797 enum L4_thread_ex_regs_flags
00798 {

```

```

00799 L4_THREAD_EX_REGS_CANCEL          = 0x10000UL,
00800 L4_THREAD_EX_REGS_TRIGGER_EXCEPTION = 0x20000UL,
00801
00802 L4_THREAD_EX_REGS_ARCH_MASK        = 0xff000000UL,
00803 };
00804
00805
00806 /* IMPLEMENTATION -----*/
00807
00808 #include <l4/sys/ipc.h>
00809 #include <l4/sys/types.h>
00810
00811 L4_INLINE l4_msgtag_t
00812 l4_thread_ex_regs_u(l4_cap_idx_t thread, l4_addr_t ip, l4_addr_t sp,
00813                    l4_umword_t flags, l4_utcb_t *utcb) L4_NOTHROW
00814 {
00815     l4_msg_regs_t *v = l4_utcb_mr_u(utcb);
00816     v->mr[0] = L4_THREAD_EX_REGS_OP | flags;
00817     v->mr[1] = ip;
00818     v->mr[2] = sp;
00819     return l4_ipc_call(thread, utcb, l4_msgtag(L4_PROTO_THREAD, 3, 0, 0), L4_IPC_NEVER);
00820 }
00821
00822 L4_INLINE l4_msgtag_t
00823 l4_thread_ex_regs_ret_u(l4_cap_idx_t thread, l4_addr_t *ip, l4_addr_t *sp,
00824                        l4_umword_t *flags, l4_utcb_t *utcb) L4_NOTHROW
00825 {
00826     l4_msg_regs_t *v = l4_utcb_mr_u(utcb);
00827     l4_msgtag_t ret = l4_thread_ex_regs_u(thread, *ip, *sp, *flags, utcb);
00828     if (l4_error_u(ret, utcb))
00829         return ret;
00830
00831     *flags = v->mr[0];
00832     *ip = v->mr[1];
00833     *sp = v->mr[2];
00834     return ret;
00835 }
00836
00837 L4_INLINE void
00838 l4_thread_control_start_u(l4_utcb_t *utcb) L4_NOTHROW
00839 {
00840     l4_msg_regs_t *v = l4_utcb_mr_u(utcb);
00841     v->mr[L4_THREAD_CONTROL_MR_IDX_FLAGS] = L4_THREAD_CONTROL_OP;
00842 }
00843
00844 L4_INLINE void
00845 l4_thread_control_pager_u(l4_cap_idx_t pager, l4_utcb_t *utcb) L4_NOTHROW
00846 {
00847     l4_msg_regs_t *v = l4_utcb_mr_u(utcb);
00848     v->mr[L4_THREAD_CONTROL_MR_IDX_FLAGS] |= L4_THREAD_CONTROL_SET_PAGER;
00849     v->mr[L4_THREAD_CONTROL_MR_IDX_PAGER] = pager;
00850 }
00851
00852 L4_INLINE void
00853 l4_thread_control_exc_handler_u(l4_cap_idx_t exc_handler,
00854                                l4_utcb_t *utcb) L4_NOTHROW
00855 {
00856     l4_msg_regs_t *v = l4_utcb_mr_u(utcb);
00857     v->mr[L4_THREAD_CONTROL_MR_IDX_FLAGS] |= L4_THREAD_CONTROL_SET_EXC_HANDLER;
00858     v->mr[L4_THREAD_CONTROL_MR_IDX_EXC_HANDLER] = exc_handler;
00859 }
00860
00861 L4_INLINE void
00862 l4_thread_control_bind_u(l4_utcb_t *thread_utcb, l4_cap_idx_t task,
00863                         l4_utcb_t *utcb) L4_NOTHROW
00864 {
00865     l4_msg_regs_t *v = l4_utcb_mr_u(utcb);
00866     v->mr[L4_THREAD_CONTROL_MR_IDX_FLAGS] |= L4_THREAD_CONTROL_BIND_TASK;
00867     v->mr[L4_THREAD_CONTROL_MR_IDX_BIND_UTCB] = (l4_addr_t)thread_utcb;
00868     v->mr[L4_THREAD_CONTROL_MR_IDX_BIND_TASK] = L4_ITEM_MAP;
00869     v->mr[L4_THREAD_CONTROL_MR_IDX_BIND_TASK + 1] = l4_obj_fpage(task, 0, L4_CAP_FPAGE_RWS).raw;
00870 }
00871
00872 L4_INLINE void
00873 l4_thread_control_alien_u(l4_utcb_t *utcb, int on) L4_NOTHROW
00874 {
00875     l4_msg_regs_t *v = l4_utcb_mr_u(utcb);
00876     v->mr[L4_THREAD_CONTROL_MR_IDX_FLAGS] |= L4_THREAD_CONTROL_ALIEN;
00877     v->mr[L4_THREAD_CONTROL_MR_IDX_FLAG_VALS] |= on ? L4_THREAD_CONTROL_ALIEN : 0;
00878 }
00879
00880 L4_INLINE l4_msgtag_t
00881 l4_thread_control_commit_u(l4_cap_idx_t thread, l4_utcb_t *utcb) L4_NOTHROW
00882 {
00883     int items = 0;
00884     if (l4_utcb_mr_u(utcb)->mr[L4_THREAD_CONTROL_MR_IDX_FLAGS] & L4_THREAD_CONTROL_BIND_TASK)
00885         items = 1;

```

```

00886     return l4_ipc_call(thread, utcb, l4_msgtag(L4_PROTO_THREAD, 6, items, 0), L4_IPC_NEVER);
00887 }
00888
00889
00890 L4_INLINE l4_msgtag_t
00891 l4_thread_yield(void) L4_NOTHROW
00892 {
00893     l4_ipc_receive(L4_INVALID_CAP, NULL, L4_IPC_BOTH_TIMEOUT_0);
00894     return l4_msgtag(0, 0, 0, 0);
00895 }
00896
00897 /* Preliminary, to be changed */
00898 L4_INLINE l4_msgtag_t
00899 l4_thread_switch_u(l4_cap_idx_t to_thread, l4_utcb_t *utcb) L4_NOTHROW
00900 {
00901     l4_msg_regs_t *v = l4_utcb_mr_u(utcb);
00902     v->mr[0] = L4_THREAD_SWITCH_OP;
00903     return l4_ipc_call(to_thread, utcb, l4_msgtag(L4_PROTO_THREAD, 1, 0, 0), L4_IPC_NEVER);
00904 }
00905
00906
00907 L4_INLINE l4_msgtag_t
00908 l4_thread_stats_time_u(l4_cap_idx_t thread, l4_kernel_clock_t *us,
00909                       l4_utcb_t *utcb) L4_NOTHROW
00910 {
00911     l4_msg_regs_t *v = l4_utcb_mr_u(utcb);
00912     l4_msgtag_t res;
00913
00914     v->mr[0] = L4_THREAD_STATS_OP;
00915
00916     res = l4_ipc_call(thread, utcb, l4_msgtag(L4_PROTO_THREAD, 1, 0, 0), L4_IPC_NEVER);
00917
00918     if (l4_msgtag_has_error(res))
00919         return res;
00920
00921     *us = v->mr64[l4_utcb_mr64_idx(0)];
00922
00923     return res;
00924 }
00925
00926 L4_INLINE l4_msgtag_t
00927 l4_thread_vcpu_resume_start_u(l4_utcb_t *utcb) L4_NOTHROW
00928 {
00929     l4_msg_regs_t *v = l4_utcb_mr_u(utcb);
00930     v->mr[0] = L4_THREAD_VCPU_RESUME_OP;
00931     return l4_msgtag(L4_PROTO_THREAD, 1, 0, 0);
00932 }
00933
00934 L4_INLINE l4_msgtag_t
00935 l4_thread_vcpu_resume_commit_u(l4_cap_idx_t thread,
00936                               l4_msgtag_t tag, l4_utcb_t *utcb) L4_NOTHROW
00937 {
00938     return l4_ipc_call(thread, utcb, tag, L4_IPC_NEVER);
00939 }
00940
00941 L4_INLINE l4_msgtag_t
00942 l4_thread_ex_regs(l4_cap_idx_t thread, l4_addr_t ip, l4_addr_t sp,
00943                  l4_umword_t flags) L4_NOTHROW
00944 {
00945     return l4_thread_ex_regs_u(thread, ip, sp, flags, l4_utcb());
00946 }
00947
00948 L4_INLINE l4_msgtag_t
00949 l4_thread_ex_regs_ret(l4_cap_idx_t thread, l4_addr_t *ip, l4_addr_t *sp,
00950                      l4_umword_t *flags) L4_NOTHROW
00951 {
00952     return l4_thread_ex_regs_ret_u(thread, ip, sp, flags, l4_utcb());
00953 }
00954
00955 L4_INLINE void
00956 l4_thread_control_start(void) L4_NOTHROW
00957 {
00958     l4_thread_control_start_u(l4_utcb());
00959 }
00960
00961 L4_INLINE void
00962 l4_thread_control_pager(l4_cap_idx_t pager) L4_NOTHROW
00963 {
00964     l4_thread_control_pager_u(pager, l4_utcb());
00965 }
00966
00967 L4_INLINE void
00968 l4_thread_control_exc_handler(l4_cap_idx_t exc_handler) L4_NOTHROW
00969 {
00970     l4_thread_control_exc_handler_u(exc_handler, l4_utcb());
00971 }
00972

```

```

00973
00974 L4_INLINE void
00975 l4_thread_control_bind(l4_utcb_t *thread_utcb, l4_cap_idx_t task) L4_NOTHROW
00976 {
00977     l4_thread_control_bind_u(thread_utcb, task, l4_utcb());
00978 }
00979
00980 L4_INLINE void
00981 l4_thread_control_alien(int on) L4_NOTHROW
00982 {
00983     l4_thread_control_alien_u(l4_utcb(), on);
00984 }
00985
00986 L4_INLINE l4_msgtag_t
00987 l4_thread_control_commit(l4_cap_idx_t thread) L4_NOTHROW
00988 {
00989     return l4_thread_control_commit_u(thread, l4_utcb());
00990 }
00991
00992
00993
00994
00995 L4_INLINE l4_msgtag_t
00996 l4_thread_switch(l4_cap_idx_t to_thread) L4_NOTHROW
00997 {
00998     return l4_thread_switch_u(to_thread, l4_utcb());
00999 }
01000
01001
01002
01003
01004 L4_INLINE l4_msgtag_t
01005 l4_thread_stats_time(l4_cap_idx_t thread, l4_kernel_clock_t *us) L4_NOTHROW
01006 {
01007     return l4_thread_stats_time_u(thread, us, l4_utcb());
01008 }
01009
01010 L4_INLINE l4_msgtag_t
01011 l4_thread_vcpu_resume_start(void) L4_NOTHROW
01012 {
01013     return l4_thread_vcpu_resume_start_u(l4_utcb());
01014 }
01015
01016 L4_INLINE l4_msgtag_t
01017 l4_thread_vcpu_resume_commit(l4_cap_idx_t thread,
01018                               l4_msgtag_t tag) L4_NOTHROW
01019 {
01020     return l4_thread_vcpu_resume_commit_u(thread, tag, l4_utcb());
01021 }
01022
01023
01024 L4_INLINE l4_msgtag_t
01025 l4_thread_register_del_irq_u(l4_cap_idx_t thread, l4_cap_idx_t irq,
01026                               l4_utcb_t *u) L4_NOTHROW
01027 {
01028     l4_msg_regs_t *m = l4_utcb_mr_u(u);
01029     m->mr[0] = L4_THREAD_REGISTER_DELETE_IRQ_OP;
01030     m->mr[1] = l4_map_obj_control(0,0);
01031     m->mr[2] = l4_obj_fpage(irq, 0, L4_CAP_FPAGE_RWS).raw;
01032     return l4_ipc_call(thread, u, l4_msgtag(L4_PROTO_THREAD, 1, 1, 0), L4_IPC_NEVER);
01033 }
01034
01035
01036 L4_INLINE l4_msgtag_t
01037 l4_thread_register_del_irq(l4_cap_idx_t thread, l4_cap_idx_t irq) L4_NOTHROW
01038 {
01039     return l4_thread_register_del_irq_u(thread, irq, l4_utcb());
01040 }
01041
01042
01043 L4_INLINE l4_msgtag_t
01044 l4_thread_vcpu_control_u(l4_cap_idx_t thread, l4_addr_t vcpu_state,
01045                           l4_utcb_t *utcb) L4_NOTHROW
01046 {
01047     l4_msg_regs_t *v = l4_utcb_mr_u(utcb);
01048     v->mr[0] = L4_THREAD_VCPU_CONTROL_OP;
01049     v->mr[1] = vcpu_state;
01050     return l4_ipc_call(thread, utcb, l4_msgtag(L4_PROTO_THREAD, 2, 0, 0), L4_IPC_NEVER);
01051 }
01052
01053 L4_INLINE l4_msgtag_t
01054 l4_thread_vcpu_control(l4_cap_idx_t thread, l4_addr_t vcpu_state) L4_NOTHROW
01055 {
01056     return l4_thread_vcpu_control_u(thread, vcpu_state, l4_utcb());
01057 }
01058 L4_INLINE l4_msgtag_t
01059 l4_thread_vcpu_control_ext_u(l4_cap_idx_t thread, l4_addr_t ext_vcpu_state,

```

```

01060                                     l4_utcb_t *utcb) L4_NOTHROW
01061 {
01062     l4_msg_regs_t *v = l4_utcb_mr_u(utcb);
01063     v->mr[0] = L4_THREAD_VCPU_CONTROL_EXT_OP;
01064     v->mr[1] = ext_vcpu_state;
01065     return l4_ipc_call(thread, utcb, l4_msgtag(L4_PROTO_THREAD, 2, 0, 0), L4_IPC_NEVER);
01066 }
01067
01068 L4_INLINE l4_msgtag_t
01069 l4_thread_vcpu_control_ext(l4_cap_idx_t thread, l4_addr_t ext_vcpu_state) L4_NOTHROW
01070 { return l4_thread_vcpu_control_ext_u(thread, ext_vcpu_state, l4_utcb()); }
01071
01072 L4_INLINE l4_msgtag_t
01073 l4_thread_modify_sender_start_u(l4_utcb_t *u) L4_NOTHROW
01074 {
01075     l4_msg_regs_t *m = l4_utcb_mr_u(u);
01076     m->mr[0] = L4_THREAD_MODIFY_SENDER_OP;
01077     return l4_msgtag(L4_PROTO_THREAD, 1, 0, 0);
01078 }
01079
01080 L4_INLINE int
01081 l4_thread_modify_sender_add_u(l4_umword_t match_mask,
01082                               l4_umword_t match,
01083                               l4_umword_t del_bits,
01084                               l4_umword_t add_bits,
01085                               l4_msgtag_t *tag, l4_utcb_t *u) L4_NOTHROW
01086 {
01087     l4_msg_regs_t *m = l4_utcb_mr_u(u);
01088     unsigned w = l4_msgtag_words(*tag);
01089     if (w >= L4_UTCB_GENERIC_DATA_SIZE - 4)
01090         return -L4_ENOMEM;
01091
01092     m->mr[w] = match_mask;
01093     m->mr[w+1] = match;
01094     m->mr[w+2] = del_bits;
01095     m->mr[w+3] = add_bits;
01096
01097     *tag = l4_msgtag(l4_msgtag_label(*tag), w + 4, 0, 0);
01098
01099     return 0;
01100 }
01101
01102 L4_INLINE l4_msgtag_t
01103 l4_thread_modify_sender_commit_u(l4_cap_idx_t thread, l4_msgtag_t tag,
01104                                  l4_utcb_t *u) L4_NOTHROW
01105 {
01106     return l4_ipc_call(thread, u, tag, L4_IPC_NEVER);
01107 }
01108
01109 L4_INLINE l4_msgtag_t
01110 l4_thread_modify_sender_start(void) L4_NOTHROW
01111 {
01112     return l4_thread_modify_sender_start_u(l4_utcb());
01113 }
01114
01115 L4_INLINE int
01116 l4_thread_modify_sender_add(l4_umword_t match_mask,
01117                             l4_umword_t match,
01118                             l4_umword_t del_bits,
01119                             l4_umword_t add_bits,
01120                             l4_msgtag_t *tag) L4_NOTHROW
01121 {
01122     return l4_thread_modify_sender_add_u(match_mask, match,
01123                                           del_bits, add_bits, tag, l4_utcb());
01124 }
01125
01126 L4_INLINE l4_msgtag_t
01127 l4_thread_modify_sender_commit(l4_cap_idx_t thread, l4_msgtag_t tag) L4_NOTHROW
01128 {
01129     return l4_thread_modify_sender_commit_u(thread, tag, l4_utcb());
01130 }
01131
01132
01133 L4_INLINE l4_msgtag_t
01134 l4_thread_register_doorbell_irq_u(l4_cap_idx_t thread, l4_cap_idx_t irq,
01135                                    l4_utcb_t *u) L4_NOTHROW
01136 {
01137     l4_msg_regs_t *m = l4_utcb_mr_u(u);
01138     m->mr[0] = L4_THREAD_REGISTER_DOORBELL_IRQ_OP;
01139     m->mr[1] = l4_map_obj_control(0, 0);
01140     m->mr[2] = l4_obj_fpage(irq, 0, L4_CAP_FPAGE_RWS).raw;
01141     return l4_ipc_call(thread, u, l4_msgtag(L4_PROTO_THREAD, 1, 1, 0),
01142                        L4_IPC_NEVER);
01143 }
01144
01145 L4_INLINE l4_msgtag_t
01146 l4_thread_register_doorbell_irq(l4_cap_idx_t thread,

```

```

01147                                     l4_cap_idx_t irq) L4_NOTHROW
01148 {
01149     return l4_thread_register_doorbell_irq_u(thread, irq, l4_utcb());
01150 }
01151
01152 #include <l4/sys/arch/thread.h>

```

## 16.139 l4/util/thread.h File Reference


Low-level Thread Functions.

```

#include <l4/sys/compiler.h>
#include <l4/sys/types.h>
#include <l4/sys/scheduler.h>
#include <l4/util/arch/thread.h>

```

Include dependency graph for thread.h:



### Macros

- `#define __L4UTIL_THREAD_FUNC(name)`

*Defines a wrapper function that sets up the registers according to the calling conventions for the architecture.*

## 16.139.1 Detailed Description

Low-level Thread Functions.

Date

1997

Author

Sebastian Schönberg

Definition in file [thread.h](#).

## 16.139.2 Macro Definition Documentation

### 16.139.2.1 \_\_L4UTIL\_THREAD\_FUNC

```
#define __L4UTIL_THREAD_FUNC(  
    name)
```

**Value:**

```
void L4_NORETURN name(void)
```

Defines a wrapper function that sets up the registers according to the calling conventions for the architecture.

Use this as a function header when starting a low-level thread where only stack and instruction pointer are in a well-defined state.

Example:

```
L4UTIL_THREAD_FUNC(helper_thread) { l4_infinite_loop(); }
```

```
thread_cap->ex_regs((l4_umword_t)helper_thread, stack_addr);
```

Definition at line 73 of file [thread.h](#).

## 16.140 thread.h

[Go to the documentation of this file.](#)

```

00001
00002
00003 /*
00004  * (c) 2003-2009 Author(s)
00005  *     economic rights: Technische Universität Dresden (Germany)
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00008
00009 #ifndef __L4_THREAD_H
00010 #define __L4_THREAD_H
00011
00012 #include <l4/sys/compiler.h>
00013 #include <l4/sys/types.h>
00014 #include <l4/sys/scheduler.h>
00015
00016 #include <l4/util/arch/thread.h>
00017
00018 L4_BEGIN_DECLS
00019
00020 L4_CV long
00021 l4util_create_thread(l4_cap_idx_t id, l4_utcb_t *thread_utcb,
00022                     l4_cap_idx_t factory,
00023                     l4_umword_t pc, l4_umword_t sp, l4_cap_idx_t pager,
00024                     l4_cap_idx_t task,
00025                     l4_cap_idx_t scheduler, l4_sched_param_t scp) L4_NOTHROW;
00026
00027 L4_END_DECLS
00028
00029 #ifndef L4UTIL_THREAD_FUNC
00030 #define __L4UTIL_THREAD_FUNC(name) void L4_NORETURN name(void)
00031 #define L4UTIL_THREAD_FUNC(name) __L4UTIL_THREAD_FUNC(name)
00032 #define __L4UTIL_THREAD_STATIC_FUNC(name) static L4_NORETURN void name(void)
00033 #define L4UTIL_THREAD_STATIC_FUNC(name) __L4UTIL_THREAD_STATIC_FUNC(name)
00034 #endif
00035
00036 #endif /* __L4_THREAD_H */

```

## 16.141 thread.h

```

00001 /*
00002  * Copyright (C) 2026 Kernkonzept GmbH.
00003  * Author(s): Jan Klötzke <jan.kloetzke@kernkonzept.com>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007 #pragma once

```

## 16.142 thread.h

```

00001 /*
00002  * Copyright (C) 2026 Kernkonzept GmbH.
00003  * Author(s): Jan Klötzke <jan.kloetzke@kernkonzept.com>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007 #pragma once


```

## 16.143 amd64/l4/util/bitops\_arch.h File Reference

amd64 bit manipulation functions



```
#include <l4/sys/compiler.h>
Include dependency graph for bitops_arch.h:
```



### 16.143.1 Detailed Description

amd64 bit manipulation functions

Definition in file [bitops\\_arch.h](#).

## 16.144 bitops\_arch.h

[Go to the documentation of this file.](#)

```

00001 /*
00002  * Copyright (C) 2000-2009 Technische Universität Dresden (Germany)
00003  * Copyright (C) 2016, 2022, 2024-2025 Kernkonzept GmbH. All rights reserved.
00004  * Author(s): Lars Reuther <reuther@os.inf.tu-dresden.de>
00005  *            Torsten Frenzel <frenzel@os.inf.tu-dresden.de>
00006  *            Frank Mehnert <frank.mehnert@kernkonzept.com>
00007  *
00008  * License: see LICENSE.spdx (in this directory or the directories above)
00009  */
00010
00016
00017 #pragma once
00018
00019 #include <l4/sys/compiler.h>
00020
00021 /*
00022  * Note: The following Assembler statement may produce wrong code:
00023  *   asm volatile ("btsl %1, %2" : "=ccc"(r) : "Jr"(63), "m"(m) : "memory");
00024  *
00025  * The compiler might chose the first variant because the bit number is smaller
00026  * than 64. However, 'bts' is encoded as 32-bit variant ('btsl') and thus only
00027  * supports immediate bit values up to 31. Some assemblers support immediate
00028  * offsets > 31 by adapting the memory address accordingly but GAS does not.
00029  * With GAS, the instruction will encode an immediate value of 63 but the CPU
00030  * will set bit 31 instead of bit 63!
00031  *
00032  * Therefore, if we would use 'btsl' instead of 'btsq', the correct constraint
00033  * for the bit number parameter would be "Ir" instead of "Jr".
00034  */
00035
00036 L4_BEGIN_DECLS
```

```

00037
00038 /* set bit */
00039 #define __L4UTIL_BITOPS_HAVE_ARCH_SET_BIT
00040 L4_INLINE void
00041 l4util_set_bit(int b, volatile l4_umword_t * dest)
00042 {
00043     __asm__ __volatile__
00044     (
00045         "lock; btsq  %1,%0  \n\t"
00046         :
00047         :
00048         "m"    (*dest), /* 0 mem, destination operand */
00049         "Jr"   ((l4_umword_t)b) /* 1, bit number */
00050         :
00051         "memory", "cc"
00052     );
00053 }
00054
00055 /* clear bit */
00056 #define __L4UTIL_BITOPS_HAVE_ARCH_CLEAR_BIT
00057 L4_INLINE void
00058 l4util_clear_bit(int b, volatile l4_umword_t * dest)
00059 {
00060     __asm__ __volatile__
00061     (
00062         "lock; btrq  %1,%0  \n\t"
00063         :
00064         :
00065         "m"    (*dest), /* 0 mem, destination operand */
00066         "Jr"   ((l4_umword_t)b) /* 1, bit number */
00067         :
00068         "memory", "cc"
00069     );
00070 }
00071
00072 /* change bit */
00073 #define __L4UTIL_BITOPS_HAVE_ARCH_COMPLEMENT_BIT
00074 L4_INLINE void
00075 l4util_complement_bit(int b, volatile l4_umword_t * dest)
00076 {
00077     __asm__ __volatile__
00078     (
00079         "lock; btcq  %1,%0  \n\t"
00080         :
00081         :
00082         "m"    (*dest), /* 0 mem, destination operand */
00083         "Jr"   ((l4_umword_t)b) /* 1, bit number */
00084         :
00085         "memory", "cc"
00086     );
00087 }
00088
00089 /* test bit */
00090 #define __L4UTIL_BITOPS_HAVE_ARCH_TEST_BIT
00091 L4_INLINE int
00092 l4util_test_bit(int b, const volatile l4_umword_t * dest)
00093 {
00094     l4_int8_t bit;
00095
00096     __asm__ __volatile__
00097     (
00098         "btq  %2,%1  \n\t"
00099         :
00100         "=@ccc" (bit) /* 0, old bit value */
00101         :
00102         "m"    (*dest), /* 1 mem, destination operand */
00103         "Jr"   ((l4_umword_t)b) /* 2, bit number */
00104         :
00105         "memory"
00106     );
00107
00108     return bit;
00109 }
00110
00111 /* bit test and set */
00112 #define __L4UTIL_BITOPS_HAVE_ARCH_BIT_TEST_AND_SET
00113 L4_INLINE int
00114 l4util_bts(int b, volatile l4_umword_t * dest)
00115 {
00116     l4_int8_t bit;
00117
00118     __asm__ __volatile__
00119     (
00120         "lock; btsq  %2,%1  \n\t"
00121         :
00122         "=@ccc" (bit) /* 0, old bit value */
00123         :

```

```

00124     "m"    (*dest),    /* 1 mem, destination operand */
00125     "Jr"   ((l4_umword_t)b) /* 2, bit number */
00126     :
00127     "memory"
00128     );
00129
00130     return bit;
00131 }
00132
00133 /* bit test and reset */
00134 #define __L4UTIL_BITOPS_HAVE_ARCH_BIT_TEST_AND_RESET
00135 L4_INLINE int
00136 l4util_btr(int b, volatile l4_umword_t * dest)
00137 {
00138     l4_int8_t bit;
00139
00140     __asm__ __volatile__
00141     (
00142         "lock; btrq %2,%1    \n\t"
00143         :
00144         "=@ccc" (bit)    /* 0,      old bit value */
00145         :
00146         "m"    (*dest),    /* 1 mem, destination operand */
00147         "Jr"   ((l4_umword_t)b) /* 2, bit number */
00148         :
00149         "memory"
00150         );
00151
00152     return bit;
00153 }
00154
00155 /* bit test and complement */
00156 #define __L4UTIL_BITOPS_HAVE_ARCH_BIT_TEST_AND_COMPLEMENT
00157 L4_INLINE int
00158 l4util_btc(int b, volatile l4_umword_t * dest)
00159 {
00160     l4_int8_t bit;
00161
00162     __asm__ __volatile__
00163     (
00164         "lock; btcq %2,%1    \n\t"
00165         :
00166         "=@ccc" (bit)    /* 0,      old bit value */
00167         :
00168         "m"    (*dest),    /* 1 mem, destination operand */
00169         "Jr"   ((l4_umword_t)b) /* 2, bit number */
00170         :
00171         "memory"
00172         );
00173
00174     return bit;
00175 }
00176
00177 /* bit scan reverse */
00178 #define __L4UTIL_BITOPS_HAVE_ARCH_BIT_SCAN_REVERSE
00179 L4_INLINE int
00180 l4util_bsr(l4_umword_t word)
00181 {
00182     l4_umword_t tmp;
00183
00184     if (L4_UNLIKELY(word == 0))
00185         return -1;
00186
00187     __asm__ __volatile__
00188     (
00189         "bsrq %1,%0 \n\t"
00190         :
00191         "=r" (tmp)    /* 0, index of most significant set bit */
00192         :
00193         "r" (word)    /* 1, argument */
00194         );
00195
00196     return tmp;
00197 }
00198
00199 /* bit scan forward */
00200 #define __L4UTIL_BITOPS_HAVE_ARCH_BIT_SCAN_FORWARD
00201 L4_INLINE int
00202 l4util_bsf(l4_umword_t word)
00203 {
00204     l4_umword_t tmp;
00205
00206     if (L4_UNLIKELY(word == 0))
00207         return -1;
00208
00209     __asm__ __volatile__
00210     (

```

```

00211     "bsfq %1,%0 \n\t"
00212     :
00213     "r" (tmp)          /* 0, index of least significant set bit */
00214     :
00215     "r" (word)         /* 1, argument */
00216     );
00217
00218     return tmp;
00219 }
00220
00221 #define __L4UTIL_BITOPS_HAVE_ARCH_FIND_FIRST_SET_BIT
00222 L4_INLINE int
00223 l4util_find_first_set_bit(const void * dest, l4_size_t size)
00224 {
00225     l4_mword_t dummy0, dummy1, res;
00226
00227     __asm__ __volatile__
00228     (
00229         "repe; scasq          \n\t"
00230         "jz     lf           \n\t"
00231         "lea    -8(%%rdi),%%rdi \n\t"
00232         "bsf    (%%rdi),%%rax  \n\t"
00233         "l:      \n\t"
00234         "sub    %%rbx,%%rdi    \n\t"
00235         "shl    $3,%%rdi      \n\t"
00236         "add    %%rdi,%%rax    \n\t"
00237         :
00238         "=a" (res), "=c" (dummy0), "=D" (dummy1)
00239         :
00240         "a" (0), "b" (dest), "c" ((size + 63) >> 6), "D" (dest)
00241         :
00242         "cc", "memory");
00243
00244     return res;
00245 }
00246
00247 #define __L4UTIL_BITOPS_HAVE_ARCH_FIND_FIRST_ZERO_BIT
00248 L4_INLINE int
00249 l4util_find_first_zero_bit(const void * dest, l4_size_t size)
00250 {
00251     l4_mword_t dummy0, dummy1, dummy2, res;
00252
00253     if (!size)
00254         return 0;
00255
00256     __asm__ __volatile__
00257     (
00258         "repe; scasq          \n\t"
00259         "je     lf           \n\t"
00260         "xor    -8(%%rdi),%%rax \n\t"
00261         "sub    $8,%%rdi      \n\t"
00262         "bsf    %%rax,%%rdx    \n\t"
00263         "l:      \n\t"
00264         "sub    %%rsi,%%rdi    \n\t"
00265         "shl    $3,%%rdi      \n\t"
00266         "add    %%rdi,%%rdx    \n\t"
00267         :
00268         "=a" (dummy0), "=c" (dummy1), "=d" (res), "=D" (dummy2)
00269         :
00270         "a" (~0UL), "c" ((size + 63) >> 6), "d" (0), "D" (dest), "S" (dest)
00271         :
00272         "cc", "memory");
00273
00274     return res;
00275 }
00276
00277 L4_END_DECLS

```

## 16.145 arm/l4/util/bitops\_arch.h File Reference

ARM specific implementation of bitops functions.

### 16.145.1 Detailed Description

ARM specific implementation of bitops functions.

Definition in file [bitops\\_arch.h](#).

## 16.146 bitops\_arch.h

[Go to the documentation of this file.](#)

```

00001
00005 /*
00006  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>
00007  *      economic rights: Technische Universität Dresden (Germany)
00008  * License: see LICENSE.spdx (in this directory or the directories above)
00009  */
00010 #ifndef __L4UTIL__ARCH_ARM__BITOPS_ARCH_H__
00011 #define __L4UTIL__ARCH_ARM__BITOPS_ARCH_H__
00012
00013
00014 #endif /* ! __L4UTIL__ARCH_ARM__BITOPS_ARCH_H__ */

```

## 16.147 x86/I4/util/bitops\_arch.h File Reference

x86 bit manipulation functions

### 16.147.1 Detailed Description

x86 bit manipulation functions

Definition in file [bitops\\_arch.h](#).

## 16.148 bitops\_arch.h

[Go to the documentation of this file.](#)

```

00001 /*
00002  * Copyright (C) 2000-2009 Technische Universität Dresden (Germany)
00003  * Copyright (C) 2016, 2022, 2024-2025 Kernkonzept GmbH. All rights reserved.
00004  * Author(s): Lars Reuther <reuther@os.inf.tu-dresden.de>
00005  *      Frank Mehnert <frank.mehnert@kernkonzept.com>
00006  *
00007  * License: see LICENSE.spdx (in this directory or the directories above)
00008  */
00009
00015
00016 #pragma once
00017
00018 L4_BEGIN_DECLS
00019
00020 /* set bit */
00021 #define __L4UTIL_BITOPS_HAVE_ARCH_SET_BIT
00022 L4_INLINE void
00023 l4util_set_bit(int b, volatile l4_umword_t * dest)
00024 {
00025     __asm__ __volatile__
00026     (
00027         "lock; btsl  %1,%0  \n\t"
00028         :
00029         :
00030         "m"    (*dest), /* 0 mem, destination operand */
00031         "Ir"   (b)      /* 1, bit number */
00032         :
00033         "memory", "cc"
00034         );
00035 }
00036
00037 /* clear bit */
00038 #define __L4UTIL_BITOPS_HAVE_ARCH_CLEAR_BIT
00039 L4_INLINE void
00040 l4util_clear_bit(int b, volatile l4_umword_t * dest)
00041 {
00042     __asm__ __volatile__
00043     (

```

```

00044     "lock; btrl %1,%0  \n\t"
00045     :
00046     :
00047     "m"    (*dest),    /* 0 mem, destination operand */
00048     "Ir"   (b)         /* 1,      bit number */
00049     :
00050     "memory", "cc"
00051     );
00052 }
00053
00054 /* change bit */
00055 #define __L4UTIL_BITOPS_HAVE_ARCH_COMPLEMENT_BIT
00056 L4_INLINE void
00057 l4util_complement_bit(int b, volatile l4_umword_t * dest)
00058 {
00059     __asm__ __volatile__
00060     (
00061         "lock; btcl %1,%0  \n\t"
00062         :
00063         :
00064         "m"    (*dest),    /* 0 mem, destination operand */
00065         "Ir"   (b)         /* 1,      bit number */
00066         :
00067         "memory", "cc"
00068         );
00069 }
00070
00071 /* test bit */
00072 #define __L4UTIL_BITOPS_HAVE_ARCH_TEST_BIT
00073 L4_INLINE int
00074 l4util_test_bit(int b, const volatile l4_umword_t * dest)
00075 {
00076     l4_int8_t bit;
00077
00078     __asm__ __volatile__
00079     (
00080         "btl %2,%1  \n\t"
00081         :
00082         "=@ccc" (bit)    /* 0,      old bit value */
00083         :
00084         "m"    (*dest),    /* 1 mem, destination operand */
00085         "Ir"   (b)         /* 2,      bit number */
00086         :
00087         "memory"
00088         );
00089
00090     return bit;
00091 }
00092
00093 /* bit test and set */
00094 #define __L4UTIL_BITOPS_HAVE_ARCH_BIT_TEST_AND_SET
00095 L4_INLINE int
00096 l4util_bts(int b, volatile l4_umword_t * dest)
00097 {
00098     l4_int8_t bit;
00099
00100     __asm__ __volatile__
00101     (
00102         "lock; btsl %2,%1  \n\t"
00103         :
00104         "=@ccc" (bit)    /* 0,      old bit value */
00105         :
00106         "m"    (*dest),    /* 1 mem, destination operand */
00107         "Ir"   (b)         /* 2,      bit number */
00108         :
00109         "memory"
00110         );
00111
00112     return bit;
00113 }
00114
00115 /* bit test and reset */
00116 #define __L4UTIL_BITOPS_HAVE_ARCH_BIT_TEST_AND_RESET
00117 L4_INLINE int
00118 l4util_btr(int b, volatile l4_umword_t * dest)
00119 {
00120     l4_int8_t bit;
00121
00122     __asm__ __volatile__
00123     (
00124         "lock; btrl %2,%1  \n\t"
00125         :
00126         "=@ccc" (bit)    /* 0,      old bit value */
00127         :
00128         "m"    (*dest),    /* 1 mem, destination operand */
00129         "Ir"   (b)         /* 2,      bit number */
00130         :

```

```

00131     "memory"
00132     );
00133
00134     return bit;
00135 }
00136
00137 /* bit test and complement */
00138 #define __L4UTIL_BITOPS_HAVE_ARCH_BIT_TEST_AND_COMPLEMENT
00139 L4_INLINE int
00140 l4util_btc(int b, volatile l4_umword_t * dest)
00141 {
00142     l4_int8_t bit;
00143
00144     __asm__ __volatile__
00145     (
00146         "lock; btl %2,%1 \n\t"
00147         :
00148         "=@ccc" (bit) /* 0, old bit value */
00149         :
00150         "m" (*dest), /* 1 mem, destination operand */
00151         "Ir" (b) /* 2, bit number */
00152         :
00153         "memory"
00154         );
00155
00156     return bit;
00157 }
00158
00159 /* bit scan reverse */
00160 #define __L4UTIL_BITOPS_HAVE_ARCH_BIT_SCAN_REVERSE
00161 L4_INLINE int
00162 l4util_bsr(l4_umword_t word)
00163 {
00164     int tmp;
00165
00166     if (L4_UNLIKELY(word == 0))
00167         return -1;
00168
00169     __asm__ __volatile__
00170     (
00171         "bsrl %1,%0 \n\t"
00172         :
00173         "=r" (tmp) /* 0, index of most significant set bit */
00174         :
00175         "r" (word) /* 1, argument */
00176         );
00177
00178     return tmp;
00179 }
00180
00181 /* bit scan forward */
00182 #define __L4UTIL_BITOPS_HAVE_ARCH_BIT_SCAN_FORWARD
00183 L4_INLINE int
00184 l4util_bsf(l4_umword_t word)
00185 {
00186     int tmp;
00187
00188     if (L4_UNLIKELY(word == 0))
00189         return -1;
00190
00191     __asm__ __volatile__
00192     (
00193         "bsfl %1,%0 \n\t"
00194         :
00195         "=r" (tmp) /* 0, index of least significant set bit */
00196         :
00197         "r" (word) /* 1, argument */
00198         );
00199
00200     return tmp;
00201 }
00202
00203 #define __L4UTIL_BITOPS_HAVE_ARCH_FIND_FIRST_SET_BIT
00204 L4_INLINE int
00205 l4util_find_first_set_bit(const void * dest, l4_size_t size)
00206 {
00207     l4_mword_t dummy0, dummy1, res;
00208
00209     __asm__ __volatile__
00210     (
00211         "repe; scasl \n\t"
00212         "jz 1f \n\t"
00213         "lea -4(%edi),%edi \n\t"
00214         "bsf (%edi),%eax \n\t"
00215         "1: \n\t"
00216         "sub %esi,%edi \n\t"
00217         "shl $3,%edi \n\t"

```

```

00218     "add  %%edi,%%eax          \n\t"
00219     :
00220     "a" (res), "c" (dummy0), "=D" (dummy1)
00221     :
00222     "a" (0), "c" ((size + 31) >> 5), "D" (dest), "S" (dest)
00223     :
00224     "cc", "memory");
00225
00226     return res;
00227 }
00228
00229 #define __L4UTIL_BITOPS_HAVE_ARCH_FIND_FIRST_ZERO_BIT
00230 L4_INLINE int
00231 l4util_find_first_zero_bit(const void * dest, l4_size_t size)
00232 {
00233     l4_mword_t dummy0, dummy1, dummy2, res;
00234
00235     if (!size)
00236         return 0;
00237
00238     __asm__ __volatile__
00239     (
00240         "repe;  scasl          \n\t"
00241         "je     1f             \n\t"
00242         "xor    -4(%%edi),%%eax \n\t"
00243         "sub    $4,%%edi        \n\t"
00244         "bsf    %%eax,%%edx     \n\t"
00245         "1:                \n\t"
00246         "sub    %%esi,%%edi     \n\t"
00247         "shl    $3,%%edi        \n\t"
00248         "add    %%edi,%%edx     \n\t"
00249         :
00250         "a" (dummy0), "c" (dummy1), "=d" (res), "=D" (dummy2)
00251         :
00252         "a" (~0UL), "c" ((size + 31) >> 5), "d" (0), "D" (dest), "S" (dest)
00253         :
00254         "cc", "memory");
00255
00256     return res;
00257 }
00258
00259 L4_END_DECLS


```

## 16.149 amd64/l4/util/cpu.h File Reference

CPU related functions.

```
#include <l4/sys/compiler.h>
```

Include dependency graph for cpu.h:





## Functions

- int [l4util\\_cpu\\_has\\_cpuid](#) (void)  
*Check whether the CPU supports the "cpuid" instruction.*
- unsigned int [l4util\\_cpu\\_capabilities](#) (void)  
*Returns the CPU capabilities if the "cpuid" instruction is available.*
- unsigned int [l4util\\_cpu\\_capabilities\\_noccheck](#) (void)  
*Returns the CPU capabilities.*
- void [l4util\\_cpu\\_cpuid](#) (unsigned long mode, unsigned long \*eax, unsigned long \*ebx, unsigned long \*ecx, unsigned long \*edx)  
*Generic CPUID access function.*

### 16.149.1 Detailed Description

CPU related functions.

#### Author

Frank Mehnert [fm3@os.inf.tu-dresden.de](mailto:fm3@os.inf.tu-dresden.de)

Definition in file [cpu.h](#).

## 16.150 cpu.h

[Go to the documentation of this file.](#)

```

00001
00006
00007 /*
00008  * (c) 2004-2009 Author(s)
00009  *      economic rights: Technische Universität Dresden (Germany)
00010  * License: see LICENSE.spdx (in this directory or the directories above)
00011  */
00012
00013 #ifndef __L4_UTIL_CPU_H
00014 #define __L4_UTIL_CPU_H
00015
00016 #include <l4/sys/compiler.h>
00017
00018 L4_BEGIN_DECLS
00019
00025
00031 L4_INLINE int      l4util_cpu_has_cpuid(void);
00032
00039 L4_INLINE unsigned int l4util_cpu_capabilities(void);
00040
00046 L4_INLINE unsigned int l4util_cpu_capabilities_noccheck(void);
00047
00051 L4_INLINE void
00052 l4util_cpu_cpuid(unsigned long mode,
00053                  unsigned long *eax, unsigned long *ebx,
00054                  unsigned long *ecx, unsigned long *edx);
00055
00057 static inline void
00058 l4util_cpu_pause(void)
00059 {
00060     __asm__ __volatile__ ("rep; nop");
00061 }
00062
00063 L4_INLINE int
00064 l4util_cpu_has_cpuid(void)
00065 {
00066     return 1;
00067 }
00068
00069 L4_INLINE void

```

```

00070 l4util_cpu_cpuid(unsigned long mode,
00071                  unsigned long *eax, unsigned long *ebx,
00072                  unsigned long *ecx, unsigned long *edx)
00073 {
00074     asm volatile("cpuid"
00075                 : "=a" (*eax),
00076                   "=b" (*ebx),
00077                   "=c" (*ecx),
00078                   "=d" (*edx)
00079                 : "a" (mode)
00080                 );
00081 }
00082
00083 L4_INLINE unsigned int
00084 l4util_cpu_capabilities_nocheck(void)
00085 {
00086     unsigned long dummy, capability;
00087
00088     /* get CPU capabilities */
00089     l4util_cpu_cpuid(1, &dummy, &dummy, &dummy, &capability);
00090
00091     return capability;
00092 }
00093
00094 L4_INLINE unsigned int
00095 l4util_cpu_capabilities(void)
00096 {
00097     if (!l4util_cpu_has_cpuid())
00098         return 0; /* CPU has not cpuid instruction */
00099
00100     return l4util_cpu_capabilities_nocheck();
00101 }
00102
00103 L4_END_DECLS
00104
00105 #endif
00106

```

## 16.151 arm/l4/util/cpu.h File Reference

CPU related functions.

### 16.151.1 Detailed Description

CPU related functions.

Author

Adam Lackorzynski [adam@os.inf.tu-dresden.de](mailto:adam@os.inf.tu-dresden.de)

Definition in file [cpu.h](#).

## 16.152 cpu.h

[Go to the documentation of this file.](#)

```

00001
00002
00003 /*
00004  * (c) 2004-2009 Author(s)
00005  *     economic rights: Technische Universität Dresden (Germany)
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00008
00009 #ifndef __L4_UTIL__ARCH_ARM__CPU_H__
00010 #define __L4_UTIL__ARCH_ARM__CPU_H__
00011
00012 /* Nothing yet */
00013
00014 #endif /* __L4_UTIL__ARCH_ARM__CPU_H__ */


```

## 16.153 x86/l4/util/cpu.h File Reference

CPU related functions.

```
#include <l4/sys/compiler.h>
```

Include dependency graph for cpu.h:



### Functions

- int [l4util\\_cpu\\_has\\_cpuid](#) (void)  
*Check whether the CPU supports the "cpuid" instruction.*
- unsigned int [l4util\\_cpu\\_capabilities](#) (void)  
*Returns the CPU capabilities if the "cpuid" instruction is available.*
- unsigned int [l4util\\_cpu\\_capabilities\\_nocheck](#) (void)  
*Returns the CPU capabilities.*
- void [l4util\\_cpu\\_cpuid](#) (unsigned long mode, unsigned long \*eax, unsigned long \*ebx, unsigned long \*ecx, unsigned long \*edx)  
*Generic CPUID access function.*

### 16.153.1 Detailed Description

CPU related functions.

#### Author

Frank Mehnert [fm3@os.inf.tu-dresden.de](mailto:fm3@os.inf.tu-dresden.de)

Definition in file [cpu.h](#).

## 16.154 cpu.h

[Go to the documentation of this file.](#)

```

00001
00006
00007 /*
00008  * (c) 2004-2009 Author(s)
00009  *     economic rights: Technische Universität Dresden (Germany)
00010  * License: see LICENSE.spdx (in this directory or the directories above)
00011  */
00012
00013 #ifndef __L4_UTIL_CPU_H
00014 #define __L4_UTIL_CPU_H
00015
00016 #include <l4/sys/compiler.h>
00017
00018 L4_BEGIN_DECLS
00019
00025
00031 L4_INLINE int          l4util_cpu_has_cpuid(void);
00032
00039 L4_INLINE unsigned int l4util_cpu_capabilities(void);
00040
00046 L4_INLINE unsigned int l4util_cpu_capabilities_nocheck(void);
00047
00051 L4_INLINE void
00052 l4util_cpu_cpuid(unsigned long mode,
00053                 unsigned long *eax, unsigned long *ebx,
00054                 unsigned long *ecx, unsigned long *edx);
00055
00057 static inline void
00058 l4util_cpu_pause(void)
00059 {
00060     __asm__ __volatile__ ("rep; nop");
00061 }
00062
00063 L4_INLINE int
00064 l4util_cpu_has_cpuid(void)
00065 {
00066     unsigned long eax;
00067
00068     asm volatile("pushl %%ebx          \t\n"
00069                 "pushfl          \t\n"
00070                 "popl %%eax          \t\n" /* get eflags */
00071                 "movl %%eax, %%ebx \t\n" /* save it */
00072                 "xorl $0x200000, %%eax \t\n" /* toggle ID bit */
00073                 "pushl %%eax          \t\n"
00074                 "popfl          \t\n" /* set again */
00075                 "pushfl          \t\n"
00076                 "popl %%eax          \t\n" /* get it again */
00077                 "xorl %%ebx, %%eax \t\n"
00078                 "pushl %%ebx          \t\n"
00079                 "popfl          \t\n" /* restore saved flags */
00080                 "popl %%ebx          \t\n"
00081                 : "=a" (eax)
00082                 : /* no input */
00083                 );
00084
00085     return eax & 0x200000;
00086 }
00087
00088 L4_INLINE void
00089 l4util_cpu_cpuid(unsigned long mode,
00090                 unsigned long *eax, unsigned long *ebx,
00091                 unsigned long *ecx, unsigned long *edx)
00092 {
00093     asm volatile("pushl %%ebx          \t\n"
00094                 "cpuid          \t\n"
00095                 "mov %%ebx, %%esi \t\n"
00096                 "popl %%ebx          \t\n"
00097                 : "=a" (*eax),
00098                   "=S" (*ebx),
00099                   "=c" (*ecx),
00100                   "=d" (*edx)
00101                 : "a" (mode));
00102 }
00103
00104 L4_INLINE unsigned int
00105 l4util_cpu_capabilities_nocheck(void)
00106 {
00107     unsigned long dummy, capability;
00108
00109     /* get CPU capabilities */
00110     l4util_cpu_cpuid(1, &dummy, &dummy, &dummy, &capability);
00111

```

```

00112     return capability;
00113 }
00114
00115 L4_INLINE unsigned int
00116 l4util_cpu_capabilities(void)
00117 {
00118     if (!l4util_cpu_has_cpuid())
00119         return 0; /* CPU has not cpuid instruction */
00120
00121     return l4util_cpu_capabilities_nocheck();
00122 }
00123
00124 L4_END_DECLS
00125
00126 #endif
00127

```

## 16.155 amd64/l4/util/mbi\_argv.h File Reference


command line handling

```

#include <l4/sys/l4int.h>
#include <l4/util/mb_info.h>
#include <l4/sys/compiler.h>

```

Include dependency graph for mbi\_argv.h:



### 16.155.1 Detailed Description

command line handling

Date

2003

Author

Frank Mehnert [fm3@os.inf.tu-dresden.de](mailto:fm3@os.inf.tu-dresden.de)

Definition in file [mbi\\_argv.h](#).

## 16.156 mbi\_argv.h

[Go to the documentation of this file.](#)

```

00001
00007
00008 /*
00009  * (c) 2003-2009 Author(s)
00010  *     economic rights: Technische Universität Dresden (Germany)
00011  * License: see LICENSE.spdx (in this directory or the directories above)
00012  */
00013
00014 #ifndef L4UTIL_MBI_ARGV
00015 #define L4UTIL_MBI_ARGV
00016
00017 #include <l4/sys/l4int.h>
00018 #include <l4/util/mb_info.h>
00019 #include <l4/sys/compiler.h>
00020
00021 L4_BEGIN_DECLS
00022
00023 L4_CV void l4util_mbi_to_argv(l4_mword_t flag, l4util_mb_info_t *mbi);
00024
00025 extern int l4util_argc;
00026 extern char *l4util_argv[];
00027
00028 L4_END_DECLS
00029
00030 #endif
00031


```

## 16.157 arm/l4/util/mbi\_argv.h File Reference

Multiboot.

```
#include <x86/l4/util/mbi_argv.h>
```

Include dependency graph for mbi\_argv.h:



### 16.157.1 Detailed Description

Multiboot.

Definition in file [mbi\\_argv.h](#).

## 16.158 mbi\_argv.h


[Go to the documentation of this file.](#)

```
00001
00005 /*
00006  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>
00007  *     economic rights: Technische Universität Dresden (Germany)
00008  * License: see LICENSE.spdx (in this directory or the directories above)
00009  */
00010 /* If this persists, move it to a generic place */
00011 #include <x86/l4/util/mbi_argv.h>
```


## 16.159 x86/l4/util/mbi\_argv.h File Reference

command line handling

```
#include <l4/sys/l4int.h>
#include <l4/util/mb_info.h>
#include <l4/sys/compiler.h>
Include dependency graph for mbi_argv.h:
```



This graph shows which files directly or indirectly include this file:



### 16.159.1 Detailed Description

command line handling

Date

2003

Author

Frank Mehnert [fm3@os.inf.tu-dresden.de](mailto:fm3@os.inf.tu-dresden.de)

Definition in file [mbi\\_argv.h](#).

## 16.160 mbi\_argv.h

[Go to the documentation of this file.](#)

```

00001
00007
00008 /*
00009  * (c) 2003-2009 Author(s)
00010  *     economic rights: Technische Universität Dresden (Germany)
00011  * License: see LICENSE.spdx (in this directory or the directories above)
00012  */
00013
00014 #ifndef L4UTIL_MBI_ARGV
00015 #define L4UTIL_MBI_ARGV
00016
00017 #include <l4/sys/l4int.h>
00018 #include <l4/util/mb_info.h>
00019 #include <l4/sys/compiler.h>
00020
00021 L4_BEGIN_DECLS
00022
00023 void l4util_mbi_to_argv(l4_mword_t flag, l4util_mb_info_t *mbi);
00024
00025 extern int l4util_argc;
00026 extern char *l4util_argv[];
00027
00028 L4_END_DECLS
00029
00030 #endif
00031


```



## 16.161 contrib/libio-io/l4/io/io.h File Reference

```
#include <l4/sys/compiler.h>
#include <l4/sys/types.h>
#include <l4/sys/linkage.h>
#include <l4/io/types.h>
```

Include dependency graph for io.h:



### Functions

- `l4_cap_idx_t l4io_request_icu` (void)  
*Request the ICU object of the client.*
- long `l4io_request_iomem` (`l4_addr_t` phys, unsigned long size, int flags, `l4_addr_t` \*virt)  
*Request an IO memory region.*
- long `l4io_request_iomem_region` (`l4_addr_t` phys, `l4_addr_t` virt, unsigned long size, int flags)  
*Request an IO memory region and map it to a specified region.*
- long `l4io_release_iomem` (`l4_addr_t` virt, unsigned long size)  
*Release an IO memory region.*
- long `l4io_request_ioport` (unsigned portnum, unsigned len)  
*Request an IO port region.*
- long `l4io_release_ioport` (unsigned portnum, unsigned len)  
*Release an IO port region.*
- `l4io_device_handle_t l4io_get_root_device` (void)  
*Get root device handle of the device bus.*
- int `l4io_iterate_devices` (`l4io_device_handle_t` \*devhandle, `l4io_device_t` \*dev, `l4io_resource_handle_t` \*reshandle)  
*Iterate over the device bus.*
- int `l4io_lookup_device` (const char \*devname, `l4io_device_handle_t` \*dev\_handle, `l4io_device_t` \*dev, `l4io_resource_handle_t` \*res\_handle)

*Find a device by name.*

- int [l4io\\_lookup\\_resource](#) (l4io\_device\_handle\_t devhandle, enum [l4io\\_resource\\_types\\_t](#) type, l4io\_resource\_handle\_t \*reshandle, [l4io\\_resource\\_t](#) \*res)

*Request a specific resource from a device description.*

- [l4\\_addr\\_t](#) [l4io\\_request\\_resource\\_iomem](#) (l4io\_device\_handle\_t devhandle, l4io\_resource\_handle\_t \*reshandle)

*Request IO memory.*

- void [l4io\\_request\\_all\\_ioports](#) (void(\*res\_cb)([l4vbus\\_resource\\_t](#) const \*res))

*Request all available IO-port resources.*

- int [l4io\\_has\\_resource](#) (enum [l4io\\_resource\\_types\\_t](#) type, [l4vbus\\_paddr\\_t](#) start, [l4vbus\\_paddr\\_t](#) end)

*Check if a resource is available.*

## 16.161.1 Function Documentation

### 16.161.1.1 l4io\_get\_root\_device()

```
l4io_device_handle_t l4io_get_root_device (
    void )    [inline]
```

Get root device handle of the device bus.

#### Returns

root device handle

Definition at line 257 of file [io.h](#).

### 16.161.1.2 l4io\_iterate\_devices()

```
int l4io_iterate_devices (
    l4io_device_handle_t * devhandle,
    l4io\_device\_t * dev,
    l4io_resource_handle_t * reshandle)
```

Iterate over the device bus.

#### Parameters

in, out	<i>devhandle</i>	Device handle to start iterating at. The next device handle is returned here.
out	<i>dev</i>	Device information, may be NULL.
out	<i>reshandle</i>	Resource handle.

#### Returns

0 on success, error code otherwise

References [L4\\_CV](#), and [L4\\_EXPORT](#).

### 16.161.1.3 l4io\_request\_all\_ioports()

```
void l4io_request_all_ioports (
    void(* res_cb ) (l4vbus_resource_t const *res))
```

Request all available IO-port resources.

#### Parameters

<code>res_cb</code>	Callback function called for every port resource found, give NULL for no callback.
---------------------	--

References [L4\\_CV](#), and [L4\\_EXPORT](#).

### 16.161.1.4 l4io\_request\_icu()

```
l4_cap_idx_t l4io_request_icu (
    void )
```

Request the ICU object of the client.

#### Returns

Client ICU object, an invalid capability selector is returned if no ICU is available.

References [L4\\_CV](#), and [L4\\_EXPORT](#).

## 16.162 io.h

[Go to the documentation of this file.](#)

```
00001
00004 /*
00005  * (c) 2008-2010 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00006  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00007  *      economic rights: Technische Universität Dresden (Germany)
00008  * License: see LICENSE.spdx (in this directory or the directories above)
00009  */
00010
00011
00012 #pragma once
00013
00014 #include <l4/sys/compiler.h>
00015 #include <l4/sys/types.h>
00016 #include <l4/sys/linkage.h>
00017 #include <l4/io/types.h>
00018
00019 L4_BEGIN_DECLS
00020
00024
00037 L4_CV long L4_EXPORT
00038 l4io_request_irq(int irqnum, l4_cap_idx_t irqcap);
00039
00046 L4_CV l4_cap_idx_t L4_EXPORT
00047 l4io_request_icu(void);
00048
00060 L4_CV long L4_EXPORT
00061 l4io_release_irq(int irqnum, l4_cap_idx_t irq_cap);
00062
00087 L4_CV long L4_EXPORT
00088 l4io_request_iomem(l4_addr_t phys, unsigned long size, int flags,
00089                   l4_addr_t *virt);
00090
00112 L4_CV long L4_EXPORT
00113 l4io_request_iomem_region(l4_addr_t phys, l4_addr_t virt,
```

```

00114             unsigned long size, int flags);
00115
00123 L4_CV long L4_EXPORT
00124 l4io_release_iomem(l4_addr_t virt, unsigned long size);
00125
00135 L4_CV long L4_EXPORT
00136 l4io_request_ioport(unsigned portnum, unsigned len);
00137
00147 L4_CV long L4_EXPORT
00148 l4io_release_ioport(unsigned portnum, unsigned len);
00149
00150
00151 /* ----- Device handling ----- */
00152
00158 L4_INLINE
00159 l4io_device_handle_t l4io_get_root_device(void);
00160
00171 L4_CV int L4_EXPORT
00172 l4io_iterate_devices(l4io_device_handle_t *devhandle,
00173                     l4io_device_t *dev, l4io_resource_handle_t *reshandle);
00174
00187 L4_CV int L4_EXPORT
00188 l4io_lookup_device(const char *devname,
00189                   l4io_device_handle_t *dev_handle,
00190                   l4io_device_t *dev, l4io_resource_handle_t *res_handle);
00191
00207 L4_CV int L4_EXPORT
00208 l4io_lookup_resource(l4io_device_handle_t devhandle,
00209                     enum l4io_resource_types_t type,
00210                     l4io_resource_handle_t *reshandle,
00211                     l4io_resource_t *res);
00212
00213
00214 /* ----- Convenience functions ----- */
00215
00228 L4_CV l4_addr_t L4_EXPORT
00229 l4io_request_resource_iomem(l4io_device_handle_t devhandle,
00230                             l4io_resource_handle_t *reshandle);
00231
00238 L4_CV void L4_EXPORT
00239 l4io_request_all_ioports(void (*res_cb)(l4vbus_resource_t const *res));
00240
00249 L4_CV int L4_EXPORT
00250 l4io_has_resource(enum l4io_resource_types_t type,
00251                  l4vbus_paddr_t start, l4vbus_paddr_t end);
00252
00253 /* ----- */
00254 /* Implementations */
00255
00256 L4_INLINE
00257 l4io_device_handle_t l4io_get_root_device(void)
00258 { return 0; }
00259
00260 L4_END_DECLS

```

## 16.163 l4/cxx/alloc.h File Reference

Alloc list.

### Data Structures

- class [L4::Alloc\\_list](#)  
*A simple list-based allocator.*

### Namespaces

- namespace [L4](#)  
*L4 low-level kernel interface.*

### 16.163.1 Detailed Description

Alloc list.

Definition in file [alloc.h](#).

## 16.164 alloc.h

[Go to the documentation of this file.](#)

```

00001
00005 /*
00006  * (c) 2004-2009 Alexander Warg <warg@os.inf.tu-dresden.de>,
00007  *      Torsten Frenzel <frenzel@os.inf.tu-dresden.de>
00008  *      economic rights: Technische Universität Dresden (Germany)
00009  *
00010  * License: see LICENSE.spdx (in this directory or the directories above)
00011  */
00012 #pragma once
00013
00014 namespace L4 {
00015
00020     class Alloc_list
00021     {
00022     public:
00023         Alloc_list() : _free(0) {}
00024         Alloc_list(void *blk, unsigned long size) : _free(0)
00025         { free( blk, size); }
00026
00027         void free(void *blk, unsigned long size);
00028         void *alloc(unsigned long size);
00029
00030     private:
00031         struct Elem
00032         {
00033             Elem *next;
00034             unsigned long size;
00035         };
00036
00037         Elem *_free;
00038     };
00039 }
```

## 16.165 arith

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00002 /*
00003  * (c) 2008-2009 Alexander Warg <warg@os.inf.tu-dresden.de>
00004  *      economic rights: Technische Universität Dresden (Germany)
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00008
00009 #pragma once
00010
00011 namespace cxx { namespace arith {
00012
00027     template<typename N, typename D>
00028     constexpr N
00029     div_ceil(N const &n, D const &d)
00030     {
00031         // Since C++11 the "quotient is truncated towards zero (fractional part is
00032         // discarded)". Thus a negative quotient is already ceiled, whereas a
00033         // positive quotient is floored. Furthermore, since C++11 the sign of the
00034         // % operator is no longer implementation defined, thus we can use n % d to
00035         // detect if the quotient is positive (n % d >= 0) and was truncated (n % d !=
00036         // 0). In that case, we add one to round to the next largest integer.
00037         return n / d + (n % d > 0);
00038     }
00039
00047     template< unsigned long V >
00048     struct Ld
00049     {
00050         enum { value = Ld<V / 2>::value + 1 };
00051     };
00052 }
```


```
00051 };
00052
00053 template<>
00054 struct Ld<0>
00055 {
00056     enum { value = ~0UL };
00057 };
00058
00059 template<>
00060 struct Ld<1>
00061 {
00062     enum { value = 0 };
00063 };
00064
00072 constexpr unsigned
00073 log2u(unsigned val)
00074 {
00075     return 8 * sizeof(val) - __builtin_clz(val) - 1;
00076 }
00077
00079 constexpr unsigned
00080 log2u(unsigned long val)
00081 {
00082     return 8 * sizeof(val) - __builtin_clzl(val) - 1;
00083 }
00084
00086 constexpr unsigned
00087 log2u(unsigned long long val)
00088 {
00089     return 8 * sizeof(val) - __builtin_clzll(val) - 1;
00090 }
00091
00100 template<typename T>
00101 constexpr unsigned
00102 log2u_ceil(T val)
00103 {
00104     return val == 1 ? 0 : log2u(val - 1) + 1;
00105 }
00106
00107 }
```

## 16.166 l4/cxx/avl\_map File Reference


AVL map.

```
#include <l4/cxx/std_alloc>
#include <l4/cxx/std_ops>
#include <l4/cxx/pair>
#include <l4/cxx/avl_set>
```

Include dependency graph for avl\_map:



This graph shows which files directly or indirectly include this file:



## Data Structures

- struct `cxx::Bits::Avl_map_get_key< KEY_TYPE >`  
*Key-getter for `Avl_map`.*
- class `cxx::Avl_map< KEY_TYPE, DATA_TYPE, COMPARE, ALLOC >`  
*AVL tree based associative container.*

## Namespaces

- namespace `cxx`  
*Our C++ library.*
- namespace `cxx::Bits`  
*Internal helpers for the cxx package.*

### 16.166.1 Detailed Description

AVL map.

Definition in file `avl_map`.

## 16.167 `avl_map`

[Go to the documentation of this file.](#)

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00006 /*
00007  * (c) 2008-2009 Alexander Warg <warg@os.inf.tu-dresden.de>
00008  *      economic rights: Technische Universität Dresden (Germany)
00009  *
00010  * License: see LICENSE.spdx (in this directory or the directories above)
00011  */
00012
00013 #pragma once
00014
00015 #include <l4/cxx/std_alloc>
00016 #include <l4/cxx/std_ops>
00017 #include <l4/cxx/pair>
00018 #include <l4/cxx/avl_set>
00019
00020 namespace cxx {
00021 namespace Bits {
00022
00023 template<typename KEY_TYPE>
00024 struct Avl_map_get_key
00025 {
00026     typedef KEY_TYPE Key_type;
00027     template<typename NODE>
00028     static Key_type const &key_of(NODE const *n)
00029     { return n->item.first; }
00030 };
00031 };
00032 }
00033
00034 template< typename KEY_TYPE, typename DATA_TYPE,
00035          template<typename A> class COMPARE = Lt_functor,
00036          template<typename B> class ALLOC = New_allocator >
00037 class Avl_map :
00038     public Bits::Base_avl_set<Pair<KEY_TYPE, DATA_TYPE>,
00039                             COMPARE<KEY_TYPE>, ALLOC,
00040                             Bits::Avl_map_get_key<KEY_TYPE> >
00041 {
00042 private:
00043     typedef Pair<KEY_TYPE, DATA_TYPE> Local_item_type;
00044     typedef Bits::Base_avl_set<Local_item_type, COMPARE<KEY_TYPE>, ALLOC,
00045                             Bits::Avl_map_get_key<KEY_TYPE> > Base_type;
00046 public:
00047     typedef COMPARE<KEY_TYPE> Key_compare;
00048     typedef KEY_TYPE Key_type;
00049     typedef DATA_TYPE Data_type;
00050     typedef typename Base_type::Node Node;
00051     typedef typename Base_type::Node_allocator Node_allocator;
00052
00053     typedef typename Base_type::Iterator Iterator;
00054     typedef typename Base_type::Iterator iterator;
00055     typedef typename Base_type::Const_iterator Const_iterator;
00056     typedef typename Base_type::Const_iterator const_iterator;
00057     typedef typename Base_type::Rev_iterator Rev_iterator;
00058     typedef typename Base_type::Rev_iterator reverse_iterator;
00059     typedef typename Base_type::Const_rev_iterator Const_rev_iterator;
00060     typedef typename Base_type::Const_rev_iterator const_reverse_iterator;

```



```

00075
00080  Avl_map(Node_allocator const &alloc = Node_allocator())
00081      : Base_type(alloc)
00082  {}
00083
00099  cxx::Pair<Iterator, int> insert(Key_type const &key, Data_type const &data)
00100  { return Base_type::insert(Pair<Key_type, Data_type>(key, data)); }
00101
00116  template<typename... Args>
00117  cxx::Pair<Iterator, int> emplace(Args &&...args)
00118  { return Base_type::emplace(cxx::forward<Args>(args)...); }
00119
00125  Data_type const &operator [] (Key_type const &key) const
00126  { return this->find_node(key)->second; }
00127
00137  Data_type &operator [] (Key_type const &key)
00138  {
00139      Node n = this->find_node(key);
00140      if (n)
00141          return const_cast<Data_type&>(n->second);
00142      else
00143          return insert(key, Data_type()).first->second;
00144  }
00145 };
00146
00147 }
00148

```

## 16.168 l4/cxx/avl\_set File Reference


AVL set.

```


#include <l4/cxx/std_alloc>
#include <l4/cxx/std_ops>
#include <l4/cxx/type_traits>
#include <l4/cxx/avl_tree>

```

Include dependency graph for avl\_set:



This graph shows which files directly or indirectly include this file:



## Data Structures

- class [cxx::Bits::Avl\\_set\\_iter< Node, Key, Node\\_op >](#)  
*Generic iterator for the AVL-tree based set.*
- struct [cxx::Bits::Avl\\_set\\_get\\_key< KEY\\_TYPE >](#)  
*Internal, key-getter for [Avl\\_set](#) nodes.*
- class [cxx::Bits::Base\\_avl\\_set< ITEM\\_TYPE, COMPARE, ALLOC, GET\\_KEY >](#)  
*AVL set with internally managed nodes.*
- class [cxx::Bits::Base\\_avl\\_set< ITEM\\_TYPE, COMPARE, ALLOC, GET\\_KEY >::Node](#)  
*A smart pointer to a tree item.*
- class [cxx::Avl\\_set< ITEM\\_TYPE, COMPARE, ALLOC >](#)  
*AVL set for simple comparable items.*

## Namespaces

- namespace [cxx](#)  
*Our C++ library.*
- namespace [cxx::Bits](#)  
*Internal helpers for the [cxx](#) package.*

## 16.168.1 Detailed Description

AVL set.

Definition in file [avl\\_set](#).

## 16.169 avl\_set

[Go to the documentation of this file.](#)

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00006 /*
00007  * (c) 2008-2009 Alexander Warg <warg@os.inf.tu-dresden.de>,
00008  *      Carsten Weinhold <weinhold@os.inf.tu-dresden.de>
00009  *      economic rights: Technische Universität Dresden (Germany)
00010  *
00011  * License: see LICENSE.spdx (in this directory or the directories above)
00012  */
00013
00014 #pragma once
00015
00016 #include <l4/cxx/std_alloc>
00017 #include <l4/cxx/std_ops>
00018 #include <l4/cxx/type_traits>
00019 #include <l4/cxx/avl_tree>
00020
00021 struct Avl_set_tester;
00022
00023 namespace cxx {
00024 namespace Bits {
00025
00034 template<typename Node, typename Key, typename Node_op>
00035 class Avl_set_iter : public __Bst_iter_b<Node, Node_op>
00036 {
00037 private:
00039     typedef __Bst_iter_b<Node, Node_op> Base;
00040
00042     typedef typename Type_traits<Key>::Non_const_type Non_const_key;
00043
00045     typedef Avl_set_iter<Node, Non_const_key, Node_op> Non_const_iter;
00046
00047     using Base::_n;
00048     using Base::_r;
00049     using Base::inc;
00050
00051 public:
00053     Avl_set_iter() = default;
00054
00059     Avl_set_iter(Node const *t) : Base(t) {}
00060
00065     Avl_set_iter(Base const &o) : Base(o) {}
00066
00068     Avl_set_iter(Non_const_iter const &o)
00069     : Base(o) {}
00070
00072     Avl_set_iter &operator = (Non_const_iter const &o)
00073     { Base::operator = (o); return *this; }
00074
00080     Key &operator * () const { return const_cast<Node*>(_n)->item; }
00081
00087     Key *operator -> () const { return &const_cast<Node*>(_n)->item; }
00088
00092     Avl_set_iter &operator ++ () { inc(); return *this; }
00093
00097     Avl_set_iter operator ++ (int)
00098     { Avl_set_iter tmp = *this; inc(); return tmp; }
00099 };
00100
00102 template<typename KEY_TYPE>
00103 struct Avl_set_get_key
00104 {
00105     typedef KEY_TYPE Key_type;
00106     template<typename NODE>
00107     static Key_type const &key_of(NODE const *n)
00108     { return n->item; }
00109 };
00110
00124 template<typename ITEM_TYPE, class COMPARE,
00125         template<typename A> class ALLOC,
00126         typename GET_KEY>
00127 class Base_avl_set
00128 {
00129     friend struct ::Avl_set_tester;
00130
00131 public:
00132     enum
00133     {
00134         E_noent = 2,
00141         E_exist = 17,
00142         E_nomem = 12,
00143         E_inval = 22
00144     };

```

```

00145
00147     typedef ITEM_TYPE Item_type;
00148
00150     typedef GET_KEY Get_key;
00151
00153     typedef typename GET_KEY::Key_type Key_type;
00154
00156     typedef typename Type_traits<Item_type>::Const_type Const_item_type;
00157
00159     typedef COMPARE Item_compare;
00160
00161 private:
00163     class _Node : public Avl_tree_node
00164     {
00165     public:
00167         Item_type item;
00168
00169         _Node() = default;
00170
00171         _Node(Item_type const &item) : Avl_tree_node(), item(item) {}
00172
00173         template<typename ...ARGS>
00174         _Node(ARGS &&...args) : Avl_tree_node(), item(cxx::forward<ARGS>(args)...)
00175         {}
00176     };
00177
00178 public:
00182     class Node
00183     {
00184     private:
00185         friend class Base_avl_set<ITEM_TYPE, COMPARE, ALLOC, GET_KEY>;
00186
00187         _Node const *_n;
00188
00189         explicit Node(_Node const *n) : _n(n) {}
00190
00191     public:
00193         Node() : _n(0) {}
00194
00200         Item_type const &operator * () { return _n->item; }
00201
00207         Item_type const *operator -> () { return _n->item; }
00208
00214         bool valid() const { return _n; }
00215
00217         operator Item_type const * () { return _n ? _n->item : 0; }
00218     };
00219
00221     typedef ALLOC<_Node> Node_allocator;
00222
00223 private:
00224     typedef Avl_tree<_Node, GET_KEY, COMPARE> Tree;
00225
00226     Tree _tree;
00227
00229     Node_allocator _alloc;
00230
00231     typedef typename Tree::Fwd_iter_ops Fwd;
00232     typedef typename Tree::Rev_iter_ops Rev;
00233
00239     void deep_copy(Base_avl_set const &o)
00240     {
00241         for (Const_iterator i = o.begin(); i != o.end(); ++i)
00242             insert(*i);
00243     }
00244
00245 public:
00246     typedef typename Type_traits<Item_type>::Param_type Item_param_type;
00247
00249     typedef Avl_set_iter<_Node, Item_type, Fwd> Iterator;
00250     typedef Iterator iterator;
00252     typedef Avl_set_iter<_Node, Const_item_type, Fwd> Const_iterator;
00253     typedef Const_iterator const_iterator;
00255     typedef Avl_set_iter<_Node, Item_type, Rev> Rev_iterator;
00256     typedef Rev_iterator reverse_iterator;
00258     typedef Avl_set_iter<_Node, Const_item_type, Rev> Const_rev_iterator;
00259     typedef Const_rev_iterator const_reverse_iterator;
00260
00268     explicit Base_avl_set(Node_allocator const &alloc = Node_allocator())
00269         : _tree(), _alloc(alloc)
00270     {}
00271
00272     ~Base_avl_set()
00273     { clear(); }
00274
00283     Base_avl_set(Base_avl_set const &o,
00284                 Node_allocator const &alloc = Node_allocator())

```

```

00285     : _tree(), _alloc(alloc)
00286     { deep_copy(o); }
00287
00295 Base_avl_set &operator = (Base_avl_set const &o)
00296 {
00297     if (this != &o)
00298     {
00299         clear();
00300         deep_copy(o);
00301     }
00302
00303     return *this;
00304 }
00305
00323 cxx::Pair<Iterator, int> insert(Item_type const &item);
00324
00343 template<typename... Args>
00344 cxx::Pair<Iterator, int> emplace(Args&&... args);
00345
00349 void clear() noexcept
00350 {
00351     _tree.remove_all([this](_Node *n)
00352     {
00353         n->~_Node();
00354         _alloc.free(n);
00355     });
00356 }
00357
00366 int remove(Key_type const &item)
00367 {
00368     _Node *n = _tree.remove(item);
00369
00370     if (n)
00371     {
00372         n->~_Node();
00373         _alloc.free(n);
00374         return 0;
00375     }
00376
00377     return -E_noent;
00378 }
00379
00384 int erase(Key_type const &item)
00385 { return remove(item); }
00386
00395 Node find_node(Key_type const &item) const
00396 { return Node(_tree.find_node(item)); }
00397
00406 Node lower_bound_node(Key_type const &key) const
00407 { return Node(_tree.lower_bound_node(key)); }
00408
00409 Node lower_bound_node(Key_type &&key) const
00410 { return Node(_tree.lower_bound_node(key)); }
00411
00417 Const_iterator begin() const { return _tree.begin(); }
00418
00424 Const_iterator end() const { return _tree.end(); }
00425
00431 Iterator begin() { return _tree.begin(); }
00432
00438 Iterator end() { return _tree.end(); }
00439
00445 Const_rev_iterator rbegin() const { return _tree.rbegin(); }
00446
00452 Const_rev_iterator rend() const { return _tree.rend(); }
00453
00459 Rev_iterator rbegin() { return _tree.rbegin(); }
00460
00466 Rev_iterator rend() { return _tree.rend(); }
00467
00468 Const_iterator find(Key_type const &item) const
00469 { return _tree.find(item); }
00470
00471 #ifdef __DEBUG_L4_AVL
00472 bool rec_dump(bool print)
00473 {
00474     return _tree.rec_dump(print);
00475 }
00476 #endif
00477 };
00478
00479 //-----
00480 /* Implementation of AVL Tree */
00481
00482 /* Insert new _Node. */
00483 template<typename Item, class Compare, template<typename A> class Alloc, typename KEY_TYPE>
00484 Pair<typename Base_avl_set<Item, Compare, Alloc, KEY_TYPE>::Iterator, int>

```

```

00485 Base_avl_set<Item, Compare, Alloc, KEY_TYPE>::insert(Item const &item)
00486 {
00487     _Node *n = _alloc.alloc();
00488     if (!n)
00489         return cxx::pair(end(), -E_nomem);
00490
00491     new (n, Nothrow()) _Node(item);
00492     Pair<_Node *, bool> err = _tree.insert(n);
00493     if (!err.second)
00494     {
00495         n->~_Node();
00496         _alloc.free(n);
00497     }
00498
00499     return cxx::pair(Iterator(typename Tree::Iterator(err.first, err.first)), err.second ? 0 :
-E_exist);
00500 }
00501
00502 /* In-place insert new _Node. */
00503 template<typename Item, class Compare, template<typename A> class Alloc, typename KEY_TYPE>
00504 template<typename... Args>
00505 Pair<typename Base_avl_set<Item, Compare, Alloc, KEY_TYPE>::Iterator, int>
00506 Base_avl_set<Item, Compare, Alloc, KEY_TYPE>::emplace(Args&&... args)
00507 {
00508     _Node *n = _alloc.alloc();
00509     if (!n)
00510         return cxx::pair(end(), -E_nomem);
00511
00512     new (n, Nothrow()) _Node(cxx::forward<Args>(args)...);
00513     Pair<_Node *, bool> err = _tree.insert(n);
00514     if (!err.second)
00515     {
00516         n->~_Node();
00517         _alloc.free(n);
00518     }
00519
00520     return cxx::pair(Iterator(typename Tree::Iterator(err.first, err.first)), err.second ? 0 :
-E_exist);
00521 }
00522
00523 } // namespace Bits
00524
00525 template<typename ITEM_TYPE, template<typename T> class COMPARE = Lt_functor,
00526         template<typename A> class ALLOC = New_allocator>
00527 class Avl_set :
00528     public Bits::Base_avl_set<ITEM_TYPE, COMPARE<ITEM_TYPE>, ALLOC,
00529                             Bits::Avl_set_get_key<ITEM_TYPE>»
00530 {
00531 private:
00532     typedef Bits::Base_avl_set<ITEM_TYPE, COMPARE<ITEM_TYPE>, ALLOC,
00533                             Bits::Avl_set_get_key<ITEM_TYPE>» Base;
00534
00535 public:
00536     typedef typename Base::Node_allocator Node_allocator;
00537     Avl_set() = default;
00538     Avl_set(Node_allocator const &alloc)
00539         : Base(alloc)
00540     {}
00541 };
00542
00543 } // namespace cxx

```

## 16.170 I4/cxx/avl\_tree File Reference


AVL tree.

```


#include "std_ops"
#include "pair"
#include "bits/bst.h"
#include "bits/bst_iter.h"

```

Include dependency graph for avl\_tree:



This graph shows which files directly or indirectly include this file:



## Data Structures

- class [cxx::Avl\\_tree\\_node](#)  
*Node of an AVL tree.*
- class [cxx::Avl\\_tree< Node, Get\\_key, Compare >](#)  
*A generic AVL tree.*

## Namespaces

- namespace [cxx](#)  
*Our C++ library.*

### 16.170.1 Detailed Description

AVL tree.

Definition in file [avl\\_tree](#).

## 16.171 avl\_tree

[Go to the documentation of this file.](#)

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00006 /*
00007  * (c) 2008-2009 Alexander Warg <warg@os.inf.tu-dresden.de>,
00008  *      Carsten Weinhold <weinhold@os.inf.tu-dresden.de>
00009  *      economic rights: Technische Universität Dresden (Germany)
00010  *
00011  * License: see LICENSE.spdx (in this directory or the directories above)
00012  */
00013
00014 #pragma once
00015
00016 #include "std_ops"
00017 #include "pair"
00018
00019 #include "bits/bst.h"
00020 #include "bits/bst_iter.h"
00021
00022 struct Avl_set_tester;
00023
00024 namespace cxx {
00025
00029 class Avl_tree_node : public Bits::Bst_node
00030 {
00031     friend struct ::Avl_set_tester;
00032
00033 private:
00034     template< typename Node, typename Get_key, typename Compare >
00035     friend class Avl_tree;
00036
00038     typedef Bits::Direction Bal;
00040     typedef Bits::Direction Dir;
00041
00042     // We are a final BST node, hide interior.
00044     using Bits::Bst_node::next;
00045     using Bits::Bst_node::next_p;
00046     using Bits::Bst_node::rotate;
00048
00050     Bal _balance;
00051
00052 protected:
00054     Avl_tree_node() = default;
00055
00056 private:
00057     Avl_tree_node(Avl_tree_node const &o) = delete;
00058     Avl_tree_node(Avl_tree_node &&o) = delete;
00059

```



```

00061     Avl_tree_node &operator = (Avl_tree_node const &o) = default;
00063     Avl_tree_node &operator = (Avl_tree_node &&o) = default;
00064
00066     explicit Avl_tree_node(bool) : Bits::Bst_node(true), _balance(Dir::N) {}
00067
00069     static Bits::Bst_node *rotate2(Bst_node **t, Bal idir, Bal pre);
00070
00072     bool balanced() const { return _balance == Bal::N; }
00073
00075     Bal balance() const { return _balance; }
00076
00078     void balance(Bal b) { _balance = b; }
00079 };
00080
00081
00098 template< typename Node, typename Get_key,
00099           typename Compare = Lt_functor<typename Get_key::Key_type> >
00100 class Avl_tree : public Bits::Bst<Node, Get_key, Compare>
00101 {
00102 private:
00103     typedef Bits::Bst<Node, Get_key, Compare> Bst;
00104
00106     using Bst::_head;
00107
00109     using Bst::k;
00110
00112     typedef typename Avl_tree_node::Bal Bal;
00114     typedef typename Avl_tree_node::Bal Dir;
00115
00116     Avl_tree(Avl_tree const &o) = delete;
00117     Avl_tree &operator = (Avl_tree const &o) = delete;
00118     Avl_tree(Avl_tree &&o) = delete;
00119     Avl_tree &operator = (Avl_tree &&o) = delete;
00120
00121 public:
00123     typedef typename Bst::Key_type Key_type;
00124     typedef typename Bst::Key_param_type Key_param_type;
00126
00127     // Grab iterator types from Bst
00130     typedef typename Bst::Iterator Iterator;
00132     typedef typename Bst::Const_iterator Const_iterator;
00134     typedef typename Bst::Rev_iterator Rev_iterator;
00136     typedef typename Bst::Const_rev_iterator Const_rev_iterator;
00138
00146     Pair<Node *, bool> insert(Node *new_node);
00147
00154     Node *remove(Key_param_type key);
00158     Node *erase(Key_param_type key) { return remove(key); }
00159
00161     Avl_tree() = default;
00162
00164     ~Avl_tree() noexcept
00165     {
00166         this->remove_all([](Node *){});
00167     }
00168
00169 #ifdef __DEBUG_L4_AVL
00170     bool rec_dump(Avl_tree_node *n, int depth, int *dp, bool print, char pfx);
00171     bool rec_dump(bool print)
00172     {
00173         int dp=0;
00174         return rec_dump(static_cast<Avl_tree_node *>(_head), 0, &dp, print, '+');
00175     }
00176 #endif
00177 };
00178
00179
00180 //-----
00181 /* IMPLEMENTATION: Bits::__Bst_iter_b */
00182
00183
00184 inline
00185 Bits::Bst_node *
00186 Avl_tree_node::rotate2(Bst_node **t, Bal idir, Bal pre)
00187 {
00188     typedef Bits::Bst_node N;
00189     typedef Avl_tree_node A;
00190     N *tmp[2] = { *t, N::next(*t, idir) };
00191     *t = N::next(tmp[1], !idir);
00192     A *n = static_cast<A*>(*t);
00193
00194     N::next(tmp[0], idir, N::next(n, !idir));
00195     N::next(tmp[1], !idir, N::next(n, idir));
00196     N::next(n, !idir, tmp[0]);
00197     N::next(n, idir, tmp[1]);
00198
00199     n->balance(Bal::N);

```

```

00200
00201     if (pre == Bal::N)
00202     {
00203         static_cast<A*>(tmp[0])->balance(Bal::N);
00204         static_cast<A*>(tmp[1])->balance(Bal::N);
00205         return nullptr;
00206     }
00207
00208     static_cast<A*>(tmp[pre != idir])->balance(!pre);
00209     static_cast<A*>(tmp[pre == idir])->balance(Bal::N);
00210
00211     return N::next(tmp[pre == idir], !pre);
00212 }
00213
00214 //-----
00215 /* Implementation of AVL Tree */
00216
00217 /* Insert new _Node. */
00218 template< typename Node, typename Get_key, class Compare>
00219 Pair<Node *, bool>
00220 Avl_tree<Node, Get_key, Compare>::insert(Node *new_node)
00221 {
00222     typedef Avl_tree_node A;
00223     typedef Bits::Bst_node N;
00224     N **t = &_head; /* search variable */
00225     N **s = &_head; /* node where rebalancing may occur */
00226     Key_param_type new_key = Get_key::key_of(new_node);
00227
00228     // search insertion point
00229     for (N *p; (p = *t);)
00230     {
00231         Dir b = this->dir(new_key, p);
00232         if (b == Dir::N)
00233             return pair(static_cast<Node*>(p), false);
00234
00235         if (!static_cast<A const *>(p)->balanced())
00236             s = t;
00237
00238         t = A::next_p(p, b);
00239     }
00240
00241     *static_cast<A*>(new_node) = A(true);
00242     *t = new_node;
00243
00244     N *n = *s;
00245     A *a = static_cast<A*>(n);
00246     if (!a->balanced())
00247     {
00248         A::Bal b(this->greater(new_key, n));
00249         if (a->balance() != b)
00250         {
00251             // ok we got in balance the shorter subtree go higher
00252             a->balance(Bal::N);
00253             // propagate the new balance down to the new node
00254             n = A::next(n, b);
00255         }
00256         else if (b == Bal(this->greater(new_key, A::next(n, b))))
00257         {
00258             // left-left or right-right case -> single rotation
00259             A::rotate(s, b);
00260             a->balance(Bal::N);
00261             static_cast<A*>(*s)->balance(Bal::N);
00262             n = A::next(*s, b);
00263         }
00264         else
00265         {
00266             // need a double rotation
00267             n = A::next(A::next(n, b), !b);
00268             n = A::rotate2(s, b, n == new_node ? Bal::N : Bal(this->greater(new_key, n)));
00269         }
00270     }
00271
00272     for (A::Bal b; n && n != new_node; static_cast<A*>(n)->balance(b), n = A::next(n, b))
00273         b = Bal(this->greater(new_key, n));
00274
00275     return pair(new_node, true);
00276 }
00277
00278
00279 /* remove an element */
00280 template< typename Node, typename Get_key, class Compare>
00281 inline
00282 Node *Avl_tree<Node, Get_key, Compare>::remove(Key_param_type key)
00283 {
00284     typedef Avl_tree_node A;
00285     typedef Bits::Bst_node N;
00286     N **q = &_head; /* search variable */

```

```

00287     N **s = &_head; /* last ('deepest') node on the search path to q
00288                     * with balance 0, at this place the rebalancing
00289                     * stops in any case */
00290     N **t = nullptr;
00291     Dir dir;
00292
00293     // find target node and rebalancing entry
00294     for (N *n; (n = *q); q = A::next_p(n, dir))
00295     {
00296         dir = Dir(this->greater(key, n));
00297         if (dir == Dir::L && !this->greater(k(n), key))
00298             /* found node */
00299             t = q;
00300
00301         if (!A::next(n, dir))
00302             break;
00303
00304         A const *a = static_cast<A const *>(n);
00305         if (a->balanced() || (a->balance() == !dir && A::next<A>(n, !dir)->balanced()))
00306             s = q;
00307     }
00308
00309     // nothing found
00310     if (!t)
00311         return nullptr;
00312
00313     A *i = static_cast<A*>(*t);
00314
00315     for (N *n; (n = *s); s = A::next_p(n, dir))
00316     {
00317         dir = Dir(this->greater(key, n));
00318
00319         if (!A::next(n, dir))
00320             break;
00321
00322         A *a = static_cast<A*>(n);
00323         // got one out of balance
00324         if (a->balanced())
00325             a->balance(!dir);
00326         else if (a->balance() == dir)
00327             a->balance(Bal::N);
00328         else
00329         {
00330             // we need rotations to get in balance
00331             Bal b = A::next<A>(n, !dir)->balance();
00332             if (b == dir)
00333                 A::rotate2(s, !dir, A::next<A>(A::next(n, !dir), dir)->balance());
00334             else
00335             {
00336                 A::rotate(s, !dir);
00337                 if (b != Bal::N)
00338                 {
00339                     a->balance(Bal::N);
00340                     static_cast<A*>(*s)->balance(Bal::N);
00341                 }
00342                 else
00343                 {
00344                     a->balance(!dir);
00345                     static_cast<A*>(*s)->balance(dir);
00346                 }
00347             }
00348             if (n == i)
00349                 t = A::next_p(*s, dir);
00350         }
00351     }
00352
00353     A *n = static_cast<A*>(*q);
00354     *t = n;
00355     *q = A::next(n, !dir);
00356     *n = *i;
00357
00358     return static_cast<Node*>(i);
00359 }
00360
00361 #ifdef __DEBUG_L4_AVL
00362 template< typename Node, typename Get_key, class Compare>
00363 bool Avl_tree<Node, Get_key, Compare>::rec_dump(Avl_tree_node *n, int depth, int *dp, bool print, char
00364 pfx)
00365 {
00366     typedef Avl_tree_node A;
00367
00368     if (!n)
00369         return true;
00370
00371     int dpx[2] = {depth, depth};
00372     bool res = true;
00373

```

```


00373     res = rec_dump(A::next<A>(n, Dir::R), depth + 1, dpx + 1, print, '/');
00374
00375     if (print)
00376     {
00377         fprintf(stderr, "%2d: [%8p] b=%1d: ", depth, n, (int)n->balance().d);
00378
00379         for (int i = 0; i < depth; ++i)
00380             std::cerr << "    ";
00381
00382         std::cerr << pfx << (static_cast<Node*>(n)->item) << std::endl;
00383     }
00384
00385     res = res & rec_dump(A::next<A>(n, Dir::L), depth + 1, dpx, print, '\\');
00386
00387     int b = dpx[1] - dpx[0];
00388
00389     if (b < 0)
00390         *dp = dpx[0];
00391     else
00392         *dp = dpx[1];
00393
00394     Bal x = n->balance();
00395     if ((b < -1 || b > 1) ||
00396         (b == 0 && x != Bal::N) ||
00397         (b == -1 && x != Bal::L) ||
00398         (b == 1 && x != Bal::R))
00399     {
00400         if (print)
00401             fprintf(stderr, "%2d: [%8p] b=%1d: balance error %d\n", depth, n, (int)n->balance().d, b);
00402         return false;
00403     }
00404     return res;
00405 }
00406 #endif
00407
00408 }
00409

```

## 16.172 l4/cxx/basic\_ostream File Reference

Basic IO stream.

This graph shows which files directly or indirectly include this file:



### Data Structures

- class [L4::IOModifier](#)  
*Modifier class for the IO stream.*

### Namespaces

- namespace [L4](#)  
*L4 low-level kernel interface.*

## Variables

- `IOModifier` const `L4::hex`  
*Modifies the stream to print numbers as hexadecimal values.*
- `IOModifier` const `L4::dec`  
*Modifies the stream to print numbers as decimal values.*

### 16.172.1 Detailed Description

Basic IO stream.

Definition in file [basic\\_ostream](#).

## 16.173 basic\_ostream

[Go to the documentation of this file.](#)

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00006 /*
00007  * (c) 2009 Alexander Warg <warg@os.inf.tu-dresden.de>
00008  *      economic rights: Technische Universität Dresden (Germany)
00009  *
00010  * License: see LICENSE.spdx (in this directory or the directories above)
00011  */
00012 #pragma once
00013
00014 namespace L4 {
00015
00022     class IOModifier
00023     {
00024     public:
00025         IOModifier(int x) : mod(x) {}
00026         bool operator == (IOModifier o) { return mod == o.mod; }
00027         bool operator != (IOModifier o) { return mod != o.mod; }
00028         int mod;
00029     };
00030
00035     class IOBackend
00036     {
00037     public:
00038         typedef int Mode;
00039
00040     protected:
00041         friend class BasicOStream;
00042
00043         IOBackend()
00044         : int_mode(10)
00045         {}
00046
00047         virtual ~IOBackend() {}
00048
00049         virtual void write(char const *str, unsigned len) = 0;
00050
00051     private:
00052         void write(IOModifier m);
00053         void write(long long int c, int len);
00054         void write(long long unsigned c, int len);
00055         void write(long long unsigned c, unsigned char base = 10,
00056                   unsigned char len = 0, char pad = ' ');
00057
00058         Mode mode() const
00059         { return int_mode; }
00060
00061         void mode(Mode m)
00062         { int_mode = m; }
00063
00064         int int_mode;
00065     };
00066
00071     class BasicOStream
00072     {
00073     public:
00074         BasicOStream(IOBackend *b)

```

```

00075     : iob(b)
00076     {}
00077
00078     void write(char const *str, unsigned len)
00079     {
00080         if (iob)
00081             iob->write(str, len);
00082     }
00083
00084     void write(long long int c, int len)
00085     {
00086         if (iob)
00087             iob->write(c, len);
00088     }
00089
00090     void write(long long unsigned c, unsigned char base = 10,
00091                unsigned char len = 0, char pad = ' ')
00092     {
00093         if (iob)
00094             iob->write(c, base, len, pad);
00095     }
00096
00097     void write(long long unsigned c, int len)
00098     {
00099         if (iob)
00100             iob->write(c, len);
00101     }
00102
00103     void write(IOModifier m)
00104     {
00105         if (iob)
00106             iob->write(m);
00107     }
00108
00109     IOBackend::Mode be_mode() const
00110     {
00111         if (iob)
00112             return iob->mode();
00113         return 0;
00114     }
00115
00116     void be_mode(IOBackend::Mode m)
00117     {
00118         if (iob)
00119             iob->mode(m);
00120     }
00121
00122 private:
00123     IOBackend *iob;
00124 };
00125
00126 class IONumFmt
00127 {
00128 public:
00129     IONumFmt(unsigned long long n, unsigned char base = 10,
00130              unsigned char len = 0, char pad = ' ')
00131         : n(n), base(base), len(len), pad(pad)
00132     {}
00133
00134     BasicOStream &print(BasicOStream &o) const;
00135
00136 private:
00137     unsigned long long n;
00138     unsigned char base, len;
00139     char pad;
00140 };
00141
00142 inline IONumFmt n_hex(unsigned long long n) { return IONumFmt(n, 16); }
00143
00144 extern IOModifier const hex;
00145
00146 extern IOModifier const dec;
00147
00148 inline
00149 BasicOStream &IONumFmt::print(BasicOStream &o) const
00150 {
00151     o.write(n, base, len, pad);
00152     return o;
00153 }
00154
00155 // Implementation
00156
00157 inline
00158 L4::BasicOStream &
00159 operator << (L4::BasicOStream &s, char const * const str)

```

```

00172 {
00173     if (!str)
00174     {
00175         s.write("(NULL)", 6);
00176         return s;
00177     }
00178
00179     unsigned l = 0;
00180     for (; str[l] != 0; l++)
00181     ;
00182     s.write(str, l);
00183     return s;
00184 }
00185
00186 inline
00187 L4::BasicOStream &
00188 operator « (L4::BasicOStream &s, signed short u)
00189 {
00190     s.write(static_cast<long long signed>(u), -1);
00191     return s;
00192 }
00193
00194 inline
00195 L4::BasicOStream &
00196 operator « (L4::BasicOStream &s, signed u)
00197 {
00198     s.write(static_cast<long long signed>(u), -1);
00199     return s;
00200 }
00201
00202 inline
00203 L4::BasicOStream &
00204 operator « (L4::BasicOStream &s, signed long u)
00205 {
00206     s.write(static_cast<long long signed>(u), -1);
00207     return s;
00208 }
00209
00210 inline
00211 L4::BasicOStream &
00212 operator « (L4::BasicOStream &s, signed long long u)
00213 {
00214     s.write(u, -1);
00215     return s;
00216 }
00217
00218 inline
00219 L4::BasicOStream &
00220 operator « (L4::BasicOStream &s, unsigned short u)
00221 {
00222     s.write(static_cast<long long unsigned>(u), -1);
00223     return s;
00224 }
00225
00226 inline
00227 L4::BasicOStream &
00228 operator « (L4::BasicOStream &s, unsigned u)
00229 {
00230     s.write(static_cast<long long unsigned>(u), -1);
00231     return s;
00232 }
00233
00234 inline
00235 L4::BasicOStream &
00236 operator « (L4::BasicOStream &s, unsigned long u)
00237 {
00238     s.write(static_cast<long long unsigned>(u), -1);
00239     return s;
00240 }
00241
00242 inline
00243 L4::BasicOStream &
00244 operator « (L4::BasicOStream &s, unsigned long long u)
00245 {
00246     s.write(u, -1);
00247     return s;
00248 }
00249
00250 inline
00251 L4::BasicOStream &
00252 operator « (L4::BasicOStream &s, void const *u)
00253 {
00254     long unsigned x = reinterpret_cast<long unsigned>(u);
00255     L4::IOBackend::Mode mode = s.be_mode();
00256     s.write(L4::hex);
00257     s.write(static_cast<long long unsigned>(x), -1);
00258     s.be_mode(mode);

```

```

00259     return s;
00260 }
00261
00262 inline
00263 L4::BasicOStream &
00264 operator « (L4::BasicOStream &s, L4::IOModifier m)
00265 {
00266     s.write(m);
00267     return s;
00268 }
00269
00270 inline
00271 L4::BasicOStream &
00272 operator « (L4::BasicOStream &s, char c)
00273 {
00274     s.write(&c, 1);
00275     return s;
00276 }
00277
00278 inline
00279 L4::BasicOStream &
00280 operator « (L4::BasicOStream &o, L4::IONumFmt const &n)
00281 { return n.print(o); }


```

## 16.174 l4/cxx/basic\_vector.h File Reference

Basic vector.

```
#include <l4/cxx/std_alloc>
```

Include dependency graph for basic\_vector.h:



### Namespaces

- namespace [cxx](#)  
*Our C++ library.*

### 16.174.1 Detailed Description

Basic vector.

Definition in file [basic\\_vector.h](#).



## 16.175 basic\_vector.h

[Go to the documentation of this file.](#)

```

00001
00005 /*
00006  * (c) 2008-2009 Alexander Warg <warg@os.inf.tu-dresden.de>
00007  *      economic rights: Technische Universität Dresden (Germany)
00008  *
00009  * License: see LICENSE.spdx (in this directory or the directories above)
00010  */
00011 #pragma once
00012
00013 #include <14/cxx/std_alloc>
00014
00015 namespace cxx {
00016
00017 template< typename T >
00018 class Basic_vector
00019 {
00020 public:
00021     Basic_vector(T *array, unsigned long capacity)
00022     : _array(array), _capacity(capacity)
00023     {
00024         for (unsigned long i = 0; i < capacity; ++i)
00025             new (&_array[i]) T();
00026     }
00027
00028 private:
00029     T *_array;
00030     unsigned long _capacity;
00031 };
00032
00033 };

```

## 16.176 bitfield

```

00001 // vi:set ft=c++: -- Mode: C++ --
00002 /*
00003  * (c) 2012 Alexander Warg <warg@os.inf.tu-dresden.de>,
00004  *      economic rights: Technische Universität Dresden (Germany)
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00008
00009 #pragma once
00010
00011 #include "type_list"
00012
00013 namespace cxx {
00014
00015 template<typename T, unsigned LSB, unsigned MSB>
00016 class Bitfield
00017 {
00018 private:
00019     typedef remove_reference_t<T> Base_type;
00020
00021     static_assert(MSB >= LSB, "boundary mismatch in bit-field definition");
00022     static_assert(MSB < sizeof(Base_type) * 8, "MSB outside of bit-field type");
00023     static_assert(LSB < sizeof(Base_type) * 8, "LSB outside of bit-field type");
00024
00025     template<unsigned BITS> struct Best_type
00026     {
00027         template< typename TY > struct Cmp { enum { value = (BITS <= sizeof(TY)*8) }; };
00028         typedef cxx::type_list<
00029             unsigned char,
00030             unsigned short,
00031             unsigned int,
00032             unsigned long,
00033             unsigned long long
00034         > Unsigned_types;
00035         typedef cxx::find_type_t<Unsigned_types, Cmp> Type;
00036     };
00037
00038 public:
00039     enum
00040     {
00041         Bits = MSB + 1 - LSB,
00042         Lsb = LSB,
00043         Msb = MSB,
00044     };
00045 };

```

```

00058
00060 static constexpr Base_type Low_mask
00061     = Base_type(~0ULL) » (sizeof(Base_type) * 8 - Bits);
00063 static constexpr Base_type Mask = Low_mask « Lsb;
00064
00071 typedef typename Best_type<Bits>::Type Bits_type;
00072
00079 typedef typename Best_type<Bits + Lsb>::Type Shift_type;
00080
00081 private:
00082     static_assert(sizeof(Bits_type)*8 >= Bits, "error finding the type to store the bits");
00083     static_assert(sizeof(Shift_type)*8 >= Bits + Lsb, "error finding the type to keep the shifted
bits");
00084     static_assert(sizeof(Bits_type) <= sizeof(Base_type), "size mismatch for Bits_type");
00085     static_assert(sizeof(Shift_type) <= sizeof(Base_type), "size mismatch for Shift_type");
00086     static_assert(sizeof(Bits_type) <= sizeof(Shift_type), "size mismatch for Shift_type and
Bits_type");
00087
00088 public:
00096 static constexpr Bits_type get(Shift_type val)
00097 { return (val » Lsb) & Low_mask; }
00098
00109 static constexpr Base_type get_unshifted(Shift_type val)
00110 { return val & Mask; }
00111
00124 static constexpr Base_type set_dirty(Base_type dest, Shift_type val)
00125 {
00126     //assert (! (val & ~Low_mask));
00127     return (dest & ~Mask) | (val « Lsb);
00128 }
00129
00144 static constexpr Base_type set_unshifted_dirty(Base_type dest, Shift_type val)
00145 {
00146     //assert (! (val & ~Mask));
00147     return (dest & ~Mask) | val;
00148 }
00149
00158 static Base_type set(Base_type dest, Bits_type val)
00159 { return set_dirty(dest, val & Low_mask); }
00160
00170 static Base_type set_unshifted(Base_type dest, Shift_type val)
00171 { return set_unshifted_dirty(dest, val & Mask); }
00172
00184 static constexpr Base_type val_dirty(Shift_type val) { return val « Lsb; }
00185
00193 static constexpr Base_type val(Bits_type val) { return val_dirty(val & Low_mask); }
00194
00203 static constexpr Base_type val_unshifted(Shift_type val) { return val & Mask; }
00204
00206 template< typename TT >
00207 class Value_base
00208 {
00209 private:
00210     TT v;
00211
00212 public:
00213     constexpr Value_base(TT t) : v(t) {}
00214     constexpr Bits_type get() const { return Bitfield::get(v); }
00215     constexpr Base_type get_unshifted() const { return Bitfield::get_unshifted(v); }
00216
00217     void set(Bits_type val) { v = Bitfield::set(v, val); }
00218     void set_dirty(Bits_type val) { v = Bitfield::set_dirty(v, val); }
00219     void set_unshifted(Shift_type val) { v = Bitfield::set_unshifted(v, val); }
00220     void set_unshifted_dirty(Shift_type val) { v = Bitfield::set_unshifted_dirty(v, val); }
00221 };
00222
00224 template< typename TT >
00225 class Value : public Value_base<TT>
00226 {
00227 public:
00228     constexpr Value(TT t) : Value_base<TT>(t) {}
00229     constexpr operator Bits_type () const { return this->get(); }
00230     constexpr Value &operator = (Bits_type val) { this->set(val); return *this; }
00231     constexpr Value &operator = (Value const &val)
00232     { this->set(val.get()); return *this; }
00233     Value(Value const &) = default;
00234 };
00235
00237 template< typename TT >
00238 class Value_unshifted : public Value_base<TT>
00239 {
00240 public:
00241     constexpr Value_unshifted(TT t) : Value_base<TT>(t) {}
00242     constexpr operator Shift_type () const { return this->get_unshifted(); }
00243     constexpr Value_unshifted &operator = (Shift_type val) { this->set_unshifted(val); return *this; }
00244     constexpr Value_unshifted &operator = (Value_unshifted const &val)
00245     { this->set_unshifted(val.get_unshifted()); return *this; }

```

```

00246     Value_unshifted(Value_unshifted const &) = default;
00247 };
00248
00250 typedef Value<Base_type &> Ref;
00252 typedef Value<Base_type volatile &> Ref_unshifted_volatile;
00254 typedef Value<Base_type const> Val;
00255
00257 typedef Value_unshifted<Base_type &> Ref_unshifted;
00259 typedef Value_unshifted<Base_type volatile &> Ref_unshifted_volatile;
00261 typedef Value_unshifted<Base_type const> Val_unshifted;
00262 };
00263
00264 #define CXX_BITFIELD_MEMBER(LSB, MSB, name, data_member) \
00265 \
00266 \
00267 typedef cxx::Bitfield<decltype(data_member), LSB, MSB> name ## _bfm_t; \
00268 \
00269 constexpr typename name ## _bfm_t::Val name() const { return data_member; } \
00270 typename name ## _bfm_t::Val name() const volatile { return data_member; } \
00271 \
00272 constexpr typename name ## _bfm_t::Ref name() { return data_member; } \
00273 typename name ## _bfm_t::Ref_volatile name() volatile { return data_member; } \
00274
00275
00276 #define CXX_BITFIELD_MEMBER_RO(LSB, MSB, name, data_member) \
00277 \
00278 \
00279 typedef cxx::Bitfield<decltype(data_member), LSB, MSB> name ## _bfm_t; \
00280 \
00281 constexpr typename name ## _bfm_t::Val name() const { return data_member; } \
00282 typename name ## _bfm_t::Val name() const volatile { return data_member; } \
00283
00284
00285 #define CXX_BITFIELD_MEMBER_UNSHIFTED(LSB, MSB, name, data_member) \
00286 \
00287 \
00288 typedef cxx::Bitfield<decltype(data_member), LSB, MSB> name ## _bfm_t; \
00289 \
00290 constexpr typename name ## _bfm_t::Val_unshifted name() const { return data_member; } \
00291 typename name ## _bfm_t::Val_unshifted name() const volatile { return data_member; } \
00292 \
00293 constexpr typename name ## _bfm_t::Ref_unshifted name() { return data_member; } \
00294 typename name ## _bfm_t::Ref_unshifted_volatile name() volatile { return data_member; } \
00295
00296
00297 #define CXX_BITFIELD_MEMBER_UNSHIFTED_RO(LSB, MSB, name, data_member) \
00298 \
00299 \
00300 typedef cxx::Bitfield<decltype(data_member), LSB, MSB> name ## _bfm_t; \
00301 \
00302 constexpr typename name ## _bfm_t::Val_unshifted name() const { return data_member; } \
00303 typename name ## _bfm_t::Val_unshifted name() const volatile { return data_member; } \
00304
00305 }

```

## 16.177 bitmap

```

00001 // vi:set ft=c++: -*- Mode: C++ -*-
00002 /*
00003  * (c) 2008-2014 Alexander Warg <warg@os.inf.tu-dresden.de>
00004  *     economic rights: Technische Universität Dresden (Germany)
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00008
00009 #pragma once
00010
00011 namespace cxx {
00012
00013 class Bitmap_base
00014 {
00015 protected:
00016     typedef unsigned long word_type;
00017
00018     enum
00019     {
00020         W_bits = sizeof(word_type) * 8,
00021         C_bits = 8,
00022     };
00023
00024     word_type *_bits;
00025
00026     static unsigned word_index(unsigned bit) { return bit / W_bits; }

```

```

00045
00053 static unsigned bit_index(unsigned bit) { return bit % W_bits; }
00054
00058 class Bit
00059 {
00060     Bitmap_base *_bm;
00061     long _bit;
00062
00063 public:
00064     Bit(Bitmap_base *bm, long bit) : _bm(bm), _bit(bit) {}
00065     Bit &operator = (bool val) { _bm->bit(_bit, val); return *this; }
00066     operator bool () const { return _bm->bit(_bit); }
00067 };
00068
00069 public:
00070     explicit Bitmap_base(void *bits) noexcept : _bits(reinterpret_cast<word_type *>(bits)) {}
00071
00073 static long words(long bits) noexcept { return (bits + W_bits - 1) / W_bits; }
00074 static long bit_buffer_bytes(long bits) noexcept
00075 { return words(bits) * W_bits / 8; }
00076
00078 template< long BITS >
00079 class Word
00080 {
00081 public:
00082     typedef unsigned long Type;
00083     enum
00084     {
00085         Size = (BITS + W_bits - 1) / W_bits
00086     };
00087 };
00088
00090 static long chars(long bits) noexcept
00091 { return (bits + C_bits - 1) / C_bits; }
00092
00094 template< long BITS >
00095 class Char
00096 {
00097 public:
00098     typedef unsigned char Type;
00099     enum
00100     {
00101         Size = (BITS + C_bits - 1) / C_bits
00102     };
00103 };
00104
00111 void bit(long bit, bool on) noexcept;
00112
00118 void clear_bit(long bit) noexcept;
00119
00127 void atomic_clear_bit(long bit) noexcept;
00128
00136 word_type atomic_get_and_clear(long bit) noexcept;
00137
00143 void set_bit(long bit) noexcept;
00144
00152 void atomic_set_bit(long bit) noexcept;
00153
00161 word_type atomic_get_and_set(long bit) noexcept;
00162
00171 word_type bit(long bit) const noexcept;
00172
00181 word_type operator [] (long bit) const noexcept
00182 { return this->bit(bit); }
00183
00191 Bit operator [] (long bit) noexcept
00192 { return Bit(this, bit); }
00193
00205 long scan_zero(long max_bit, long start_bit = 0) const noexcept;
00206
00207 void *bit_buffer() const noexcept { return _bits; }
00208
00209 protected:
00210     static int _bzl(unsigned long w) noexcept;
00211 };
00212
00213
00219 template<int BITS>
00220 class Bitmap : public Bitmap_base
00221 {
00222 private:
00223     char _bits[Bitmap_base::Char<BITS>::Size];
00224
00225 public:
00227     Bitmap() noexcept : Bitmap_base(_bits) {}
00228     Bitmap(Bitmap<BITS> const &o) noexcept : Bitmap_base(_bits)
00229     { __builtin_memcpy(_bits, o._bits, sizeof(_bits)); }

```

```

00242     long scan_zero(long start_bit = 0) const noexcept;
00243
00244     void clear_all()
00245     { __builtin_memset(_bits, 0, sizeof(_bits)); }
00246 };
00247
00248
00249 inline
00250 void
00251 Bitmap_base::bit(long bit, bool on) noexcept
00252 {
00253     long idx = word_index(bit);
00254     long b   = bit_index(bit);
00255     _bits[idx] = (_bits[idx] & ~(1UL << b)) | (static_cast<unsigned long>(on) << b);
00256 }
00257
00258 inline
00259 void
00260 Bitmap_base::clear_bit(long bit) noexcept
00261 {
00262     long idx = word_index(bit);
00263     long b   = bit_index(bit);
00264     _bits[idx] &= ~(1UL << b);
00265 }
00266
00267 inline
00268 void
00269 Bitmap_base::atomic_clear_bit(long bit) noexcept
00270 {
00271     long idx = word_index(bit);
00272     long b   = bit_index(bit);
00273     word_type mask = 1UL << b;
00274     __atomic_and_fetch(&_bits[idx], ~mask, __ATOMIC_RELAXED);
00275 }
00276
00277 inline
00278 Bitmap_base::word_type
00279 Bitmap_base::atomic_get_and_clear(long bit) noexcept
00280 {
00281     long idx = word_index(bit);
00282     long b   = bit_index(bit);
00283     word_type mask = 1UL << b;
00284     return __atomic_fetch_and(&_bits[idx], ~mask, __ATOMIC_RELAXED) & mask;
00285 }
00286
00287 inline
00288 void
00289 Bitmap_base::set_bit(long bit) noexcept
00290 {
00291     long idx = word_index(bit);
00292     long b   = bit_index(bit);
00293     _bits[idx] |= (1UL << b);
00294 }
00295
00296 inline
00297 void
00298 Bitmap_base::atomic_set_bit(long bit) noexcept
00299 {
00300     long idx = word_index(bit);
00301     long b   = bit_index(bit);
00302     word_type mask = 1UL << b;
00303     __atomic_or_fetch(&_bits[idx], mask, __ATOMIC_RELAXED);
00304 }
00305
00306 inline
00307 Bitmap_base::word_type
00308 Bitmap_base::atomic_get_and_set(long bit) noexcept
00309 {
00310     long idx = word_index(bit);
00311     long b   = bit_index(bit);
00312     word_type mask = 1UL << b;
00313     return __atomic_fetch_or(&_bits[idx], mask, __ATOMIC_RELAXED) & mask;
00314 }
00315
00316 inline
00317 Bitmap_base::word_type
00318 Bitmap_base::bit(long bit) const noexcept
00319 {
00320     long idx = word_index(bit);
00321     long b   = bit_index(bit);
00322     return _bits[idx] & (1UL << b);
00323 }
00324
00325 inline
00326 int
00327 Bitmap_base::_bzl(unsigned long w) noexcept
00328 {

```

```

00329     for (int i = 0; i < W_bits; ++i, w >>= 1)
00330     {
00331         if ((w & 1) == 0)
00332             return i;
00333     }
00334     return -1;
00335 }
00336
00337 inline
00338 long
00339 Bitmap_base::scan_zero(long max_bit, long start_bit) const noexcept
00340 {
00341     if (!(operator [] (start_bit)))
00342         return start_bit;
00343
00344     long idx = word_index(start_bit);
00345
00346     max_bit -= start_bit & ~(W_bits - 1);
00347
00348     for (; max_bit > 0; max_bit -= W_bits, ++idx)
00349     {
00350         if (_bits[idx] == 0)
00351             return idx * W_bits;
00352
00353         if (_bits[idx] != ~0UL)
00354         {
00355             long zbit = _bzl(_bits[idx]);
00356             return zbit < max_bit ? idx * W_bits + zbit : -1;
00357         }
00358     }
00359
00360     return -1;
00361 }
00362
00363 template<int BITS> inline
00364 long
00365 Bitmap<BITS>::scan_zero(long start_bit) const noexcept
00366 {
00367     return Bitmap_base::scan_zero(BITS, start_bit);
00368 }
00369
00370 };

```

## 16.178 I4/cxx/bits/bst.h File Reference


AVL tree.

```


#include "../type_traits"
#include "bst_base.h"
#include "bst_iter.h"

```

Include dependency graph for bst.h:



This graph shows which files directly or indirectly include this file:



## Data Structures

- class `cxx::Bits::Bst< Node, Get_key, Compare >`  
*Basic binary search tree (BST).*

## Namespaces

- namespace `cxx`  
*Our C++ library.*
- namespace `cxx::Bits`  
*Internal helpers for the cxx package.*

### 16.178.1 Detailed Description

AVL tree.

Definition in file [bst.h](#).

## 16.179 bst.h

[Go to the documentation of this file.](#)

```

00001 // vi:ft=cpp
00002 /*
00003  * (c) 2008-2009 Alexander Warg <warg@os.inf.tu-dresden.de>,
00004  *      Carsten Weinhold <weinhold@os.inf.tu-dresden.de>
00005  *      economic rights: Technische Universität Dresden (Germany)
00006  *
00007  * License: see LICENSE.spdx (in this directory or the directories above)
00008  */
00009 #pragma once
00010
00011 #include "../type_traits"
00012 #include "bst_base.h"
00013 #include "bst_iter.h"
00014
00015 struct Avl_set_tester;
00016
00017 namespace cxx { namespace Bits {
00018
00019 template< typename Node, typename Get_key, typename Compare >
00020 class Bst
00021 {
00022     friend struct ::Avl_set_tester;
00023 private:
00024     typedef Direction Dir;
00025
00026     struct Fwd
00027     {
00028         static Node *child(Node const *n, Direction d)
00029         { return Bst_node::next<Node>(n, d); }
00030
00031         static bool cmp(Node const *l, Node const *r)
00032         { return Compare()(Get_key::key_of(l), Get_key::key_of(r)); }
00033     };
00034
00035     struct Rev
00036     {
00037         static Node *child(Node const *n, Direction d)
00038         { return Bst_node::next<Node>(n, !d); }
00039
00040         static bool cmp(Node const *l, Node const *r)
00041         { return Compare()(Get_key::key_of(r), Get_key::key_of(l)); }
00042     };
00043
00044 public:
00045     typedef typename Get_key::Key_type Key_type;

```



```

00062     typedef typename Type_traits<Key_type>::Param_type Key_param_type;
00063
00065     typedef Fwd Fwd_iter_ops;
00067     typedef Rev Rev_iter_ops;
00068
00070
00072     typedef __Bst_iter<Node, Node, Fwd> Iterator;
00074     typedef __Bst_iter<Node, Node const, Fwd> Const_iterator;
00076     typedef __Bst_iter<Node, Node, Rev> Rev_iterator;
00078     typedef __Bst_iter<Node, Node const, Rev> Const_rev_iterator;
00080
00081 protected:
00090
00092     Bst_node *_head;
00093
00095     Bst() : _head(nullptr) {}
00096
00098     Node *head() const { return static_cast<Node*>(_head); }
00099
00101     static Key_type k(Bst_node const *n)
00102     { return Get_key::key_of(static_cast<Node const *>(n)); }
00103
00112     static Dir dir(Key_param_type l, Key_param_type r)
00113     {
00114         Compare cmp;
00115         Dir d(cmp(r, l));
00116         if (d == Direction::L && !cmp(l, r))
00117             return Direction::N;
00118         return d;
00119     }
00120
00129     static Dir dir(Key_param_type l, Bst_node const *r)
00130     { return dir(l, k(r)); }
00131
00133     static bool greater(Key_param_type l, Key_param_type r)
00134     { return Compare()(r, l); }
00135
00137     static bool greater(Key_param_type l, Bst_node const *r)
00138     { return greater(l, k(r)); }
00139
00141     static bool greater(Bst_node const *l, Bst_node const *r)
00142     { return greater(k(l), k(r)); }
00144
00151     template<typename FUNC>
00152     static void remove_tree(Bst_node *head, FUNC &&callback)
00153     {
00154         if (Bst_node *n = Bst_node::next(head, Dir::L))
00155             remove_tree(n, callback);
00156
00157         if (Bst_node *n = Bst_node::next(head, Dir::R))
00158             remove_tree(n, callback);
00159
00160         callback(static_cast<Node *>(head));
00161     }
00162
00163 public:
00164
00173     Const_iterator begin() const { return Const_iterator(head()); }
00178     Const_iterator end() const { return Const_iterator(); }
00179
00184     Iterator begin() { return Iterator(head()); }
00189     Iterator end() { return Iterator(); }
00190
00195     Const_rev_iterator rbegin() const { return Const_rev_iterator(head()); }
00200     Const_rev_iterator rend() const { return Const_rev_iterator(); }
00201
00206     Rev_iterator rbegin() { return Rev_iterator(head()); }
00211     Rev_iterator rend() { return Rev_iterator(); }
00213
00214
00219
00225     Node *find_node(Key_param_type key) const;
00226
00233     Node *lower_bound_node(Key_param_type key) const;
00234
00241     Const_iterator find(Key_param_type key) const;
00242
00251     template<typename FUNC>
00252     void remove_all(FUNC &&callback)
00253     {
00254         if (!_head)
00255             return;
00256
00257         Bst_node *head = _head;
00258         _head = nullptr;
00259         remove_tree(head, cxx::forward<FUNC>(callback));
00260     }

```

```


00261
00262
00264 };
00265
00266 /* find an element */
00267 template< typename Node, typename Get_key, class Compare>
00268 inline
00269 Node *
00270 Bst<Node, Get_key, Compare>::find_node(Key_param_type key) const
00271 {
00272     Dir d;
00273
00274     for (Bst_node *q = _head; q; q = Bst_node::next(q, d))
00275     {
00276         d = dir(key, q);
00277         if (d == Dir::N)
00278             return static_cast<Node*>(q);
00279     }
00280     return nullptr;
00281 }
00282
00283 template< typename Node, typename Get_key, class Compare>
00284 inline
00285 Node *
00286 Bst<Node, Get_key, Compare>::lower_bound_node(Key_param_type key) const
00287 {
00288     Dir d;
00289     Bst_node *r = nullptr;
00290
00291     for (Bst_node *q = _head; q; q = Bst_node::next(q, d))
00292     {
00293         d = dir(key, q);
00294         if (d == Dir::L)
00295             r = q; // found a node greater than key
00296         else if (d == Dir::N)
00297             return static_cast<Node*>(q);
00298     }
00299     return static_cast<Node*>(r);
00300 }
00301
00302 /* find an element */
00303 template< typename Node, typename Get_key, class Compare>
00304 inline
00305 typename Bst<Node, Get_key, Compare>::Const_iterator
00306 Bst<Node, Get_key, Compare>::find(Key_param_type key) const
00307 {
00308     Bst_node *q = _head;
00309     Bst_node *r = q;
00310
00311     for (Dir d; q; q = Bst_node::next(q, d))
00312     {
00313         d = dir(key, q);
00314         if (d == Dir::N)
00315             return Iterator(static_cast<Node*>(q), static_cast<Node *>(r));
00316
00317         if (d != Dir::L && q == r)
00318             r = Bst_node::next(q, d);
00319     }
00320     return Iterator();
00321 }
00322
00323 }}

```

## 16.180 I4/cxx/bits/bst\_base.h File Reference

AVL tree.

This graph shows which files directly or indirectly include this file:



## Data Structures

- struct [cxx::Bits::Direction](#)  
*The direction to go in a binary search tree.*
- class [cxx::Bits::Bst\\_node](#)  
*Basic type of a node in a binary search tree (BST).*

## Namespaces

- namespace [cxx](#)  
*Our C++ library.*
- namespace [cxx::Bits](#)  
*Internal helpers for the cxx package.*

## 16.180.1 Detailed Description

AVL tree.

Definition in file [bst\\_base.h](#).

## 16.181 bst\_base.h

[Go to the documentation of this file.](#)

```

00001 // vi:ft=cpp
00006 /*
00007  * (c) 2008-2009 Alexander Warg <warg@os.inf.tu-dresden.de>,
00008  *      Carsten Weinhold <weinhold@os.inf.tu-dresden.de>
00009  *      economic rights: Technische Universität Dresden (Germany)
00010  *
00011  * License: see LICENSE.spdx (in this directory or the directories above)
00012  */
00013
00014 #pragma once
00015
00016 /*
00017  * This file contains very basic bits for implementing binary search trees
00018  */
00019 namespace cxx {
00023 namespace Bits {
00024
00028 struct Direction
00029 {
00031     enum Direction_e
00032     {
00033         L = 0,
00034         R = 1,
00035         N = 2
00036     };
00037     unsigned char d;
00038
00040     Direction() = default;
00041
00043     Direction(Direction_e d) : d(d) {}
00044
00046     explicit Direction(bool b) : d(Direction_e(b)) /*d(b ? R : L)*/ {}
00047
00052     Direction operator ! () const { return Direction(!d); }
00053
00055
00057     bool operator == (Direction_e o) const { return d == o; }
00059     bool operator != (Direction_e o) const { return d != o; }
00061     bool operator == (Direction o) const { return d == o.d; }
00063     bool operator != (Direction o) const { return d != o.d; }
00065 };
00066
00070 class Bst_node
00071 {
00072     // all BSTs are friends
00073     template< typename Node, typename Get_key, typename Compare >
00074     friend class Bst;
00075
00076 protected:
00085
00087     static Bst_node *next(Bst_node const *p, Direction d)
00088     { return p->_c[d.d]; }
00089
00091     static void next(Bst_node *p, Direction d, Bst_node *n)
00092     { p->_c[d.d] = n; }
00093
00095     static Bst_node **next_p(Bst_node *p, Direction d)
00096     { return &p->_c[d.d]; }
00097
00099     template< typename Node > static
00100     Node *next(Bst_node const *p, Direction d)
00101     { return static_cast<Node *>(p->_c[d.d]); }
00102
00104     static void rotate(Bst_node **t, Direction idir);
00106
00107 private:
00108     Bst_node *_c[2];
00109
00110 protected:

```


```
00112  Bst_node() {}
00113
00115  explicit Bst_node(bool) { _c[0] = _c[1] = 0; }
00116 };
00117
00118 inline
00119 void
00120 Bst_node::rotate(Bst_node **t, Direction idir)
00121 {
00122     Bst_node *tmp = *t;
00123     *t = next(tmp, idir);
00124     next(tmp, idir, next(*t, !idir));
00125     next(*t, !idir, tmp);
00126 }
00127
00128 }
```

## 16.182 I4/cxx/bits/bst\_iter.h File Reference


AVL tree.

```
#include "bst_base.h"
```

Include dependency graph for bst\_iter.h:



This graph shows which files directly or indirectly include this file:



## Namespaces

- namespace `cxx`  
*Our C++ library.*
- namespace `cxx::Bits`  
*Internal helpers for the cxx package.*

### 16.182.1 Detailed Description

AVL tree.

Definition in file `bst_iter.h`.

## 16.183 bst\_iter.h

[Go to the documentation of this file.](#)

```

00001 // vi:ft=cpp
00002 /*
00003  * (c) 2008-2009 Alexander Warg <warg@os.inf.tu-dresden.de>,
00004  *      Carsten Weinhold <weinhold@os.inf.tu-dresden.de>
00005  *      economic rights: Technische Universität Dresden (Germany)
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00008
00009 #pragma once
00010
00011 #include "bst_base.h"
00012
00013 namespace cxx { namespace Bits {
00014
00015     template< typename Node, typename Node_op >
00016     class __Bst_iter_b
00017     {
00018     protected:
00019         typedef Direction Dir;
00020         Node const *_n;
00021         Node const *_r;
00022
00023         __Bst_iter_b() : _n(0), _r(0) {}
00024
00025         __Bst_iter_b(Node const *t)
00026             : _n(t), _r(_n)
00027         { _downmost(); }
00028
00029         __Bst_iter_b(Node const *t, Node const *r)
00030             : _n(t), _r(r)
00031         {}
00032
00033         inline void _downmost();
00034
00035         inline void inc();
00036
00037     public:
00038         bool operator == (__Bst_iter_b const &o) const { return _n == o._n; }
00039         bool operator != (__Bst_iter_b const &o) const { return _n != o._n; }
00040     };
00041
00042     template< typename Node, typename Node_type, typename Node_op >
00043     class __Bst_iter : public __Bst_iter_b<Node, Node_op>
00044     {
00045     private:
00046         typedef __Bst_iter_b<Node, Node_op> Base;
00047         using Base::_n;
00048         using Base::_r;
00049         using Base::inc;
00050
00051     public:
00052         __Bst_iter() {}
00053
00054         __Bst_iter(Node const *t) : Base(t) {}
00055         __Bst_iter(Node const *t, Node const *r) : Base(t, r) {}
00056
00057         // template<typename Key2>
00058         __Bst_iter(Base const &o) : Base(o) {}
00059
00060         Node_type &operator * () const { return *const_cast<Node *>(_n); }
00061         Node_type *operator -> () const { return const_cast<Node *>(_n); }
00062         __Bst_iter &operator ++ () { inc(); return *this; }
00063         __Bst_iter &operator ++ (int)
00064         { __Bst_iter tmp = *this; inc(); return tmp; }
00065     };
00066
00067 //-----
00068 /* IMPLEMENTATION: __Bst_iter_b */
00069
00070 template< typename Node, typename Node_op>
00071 inline
00072 void __Bst_iter_b<Node, Node_op>::_downmost()
00073 {
00074     while (_n)
00075     {
00076         Node *n = Node_op::child(_n, Dir::L);
00077         if (n)
00078             _n = n;
00079         else

```

```

00134     return;
00135     }
00136 }
00137
00138 template< typename Node, typename Node_op>
00139 void __Bst_iter_b<Node, Node_op>::inc()
00140 {
00141     if (!_n)
00142         return;
00143
00144     if (_n == _r)
00145     {
00146         _r = _n = Node_op::child(_r, Dir::R);
00147         _downmost();
00148         return;
00149     }
00150
00151     if (Node_op::child(_n, Dir::R))
00152     {
00153         _n = Node_op::child(_n, Dir::R);
00154         _downmost();
00155         return;
00156     }
00157
00158     Node const *q = _r;
00159     Node const *p = _r;
00160     while (1)
00161     {
00162         if (Node_op::cmp(_n, q))
00163         {
00164             p = q;
00165             q = Node_op::child(q, Dir::L);
00166         }
00167         else if (_n == q || Node_op::child(q, Dir::R) == _n)
00168         {
00169             _n = p;
00170             return;
00171         }
00172         else
00173             q = Node_op::child(q, Dir::R);
00174     }
00175 }
00176
00177 }}

```

## 16.184 list\_basics.h

```

00001 /*
00002  * (c) 2011 Alexander Warg <warg@os.inf.tu-dresden.de>
00003  *     economic rights: Technische Universität Dresden (Germany)
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007
00008 #pragma once
00009
00010 namespace cxx { namespace Bits {
00011
00012     template< typename T >
00013     class List_iterator_end_ptr
00014     {
00015     private:
00016         template< typename U > friend class Basic_list;
00017         static void * const _end;
00018     };
00019
00020     template< typename T >
00021     void * const List_iterator_end_ptr<T>::_end = nullptr;
00022
00023     template< typename VALUE_T, typename TYPE >
00024     struct Basic_list_policy
00025     {
00026         typedef VALUE_T *Value_type;
00027         typedef VALUE_T const *Const_value_type;
00028         typedef TYPE **Type;
00029         typedef TYPE *Const_type;
00030         typedef TYPE *Head_type;
00031         typedef TYPE Item_type;
00032
00033         static Type next(Type c) { return &(*c)->_n; }
00034         static Const_type next(Const_type c) { return c->_n; }
00035     };
00036

```



```

00038 template< typename POLICY >
00039 class Basic_list
00040 {
00041     Basic_list(Basic_list const &) = delete;
00042     void operator = (Basic_list const &) = delete;
00043
00044 public:
00045     typedef typename POLICY::Value_type Value_type;
00046     typedef typename POLICY::Const_value_type Const_value_type;
00047
00048     class Iterator
00049     {
00050     private:
00051         typedef typename POLICY::Type Internal_type;
00052
00053     public:
00054         typedef typename POLICY::Value_type value_type;
00055         typedef typename POLICY::Value_type Value_type;
00056
00057         Value_type operator * () const { return static_cast<Value_type>(*_c); }
00058         Value_type operator -> () const { return static_cast<Value_type>(*_c); }
00059         Iterator operator ++ () { _c = POLICY::next(_c); return *this; }
00060
00061         bool operator == (Iterator const &o) const { return *_c == *o._c; }
00062         bool operator != (Iterator const &o) const { return !operator == (o); }
00063
00064         Iterator() : _c(__end()) {}
00065
00066     private:
00067         friend class Basic_list;
00068         static Internal_type __end()
00069         {
00070             union X { Internal_type l; void * const *v; } z;
00071             z.v = &Bits::List_iterator_end_ptr<void>::_end;
00072             return z.l;
00073         }
00074
00075         explicit Iterator(Internal_type i) : _c(i) {}
00076
00077         Internal_type _c;
00078     };
00079
00080     class Const_iterator
00081     {
00082     private:
00083         typedef typename POLICY::Const_type Internal_type;
00084
00085     public:
00086         typedef typename POLICY::Value_type value_type;
00087         typedef typename POLICY::Value_type Value_type;
00088
00089         Value_type operator * () const { return static_cast<Value_type>(_c); }
00090         Value_type operator -> () const { return static_cast<Value_type>(_c); }
00091         Const_iterator operator ++ () { _c = POLICY::next(_c); return *this; }
00092
00093         friend bool operator == (Const_iterator const &lhs, Const_iterator const &rhs)
00094         { return lhs._c == rhs._c; }
00095         friend bool operator != (Const_iterator const &lhs, Const_iterator const &rhs)
00096         { return lhs._c != rhs._c; }
00097
00098         Const_iterator() {}
00099         Const_iterator(Iterator const &o) : _c(*o) {}
00100
00101     private:
00102         friend class Basic_list;
00103
00104         explicit Const_iterator(Internal_type i) : _c(i) {}
00105
00106         Internal_type _c;
00107     };
00108
00109     // BSS allocation
00110     explicit Basic_list(bool) {}
00111     Basic_list() : _f(nullptr) {}
00112
00113     Basic_list(Basic_list &o) : _f(o._f)
00114     {
00115         o.clear();
00116     }
00117
00118     Basic_list &operator = (Basic_list &o)
00119     {
00120         _f = o._f;
00121         o.clear();
00122         return *this;
00123     }
00124

```

```

00126 bool empty() const { return !_f; }
00128 Value_type front() const { return static_cast<Value_type>(_f); }
00129
00135 void clear() { _f = nullptr; }
00136
00138 Iterator begin() { return Iterator(&_f); }
00140 Const_iterator begin() const { return Const_iterator(_f); }
00148 static Const_iterator iter(Const_value_type c) { return Const_iterator(c); }
00150 Const_iterator end() const { return Const_iterator(nullptr); }
00152 Iterator end() { return Iterator(); }
00153
00154 protected:
00155 static typename POLICY::Type __get_internal(Iterator const &i) { return i._c; }
00156 static Iterator __iter(typename POLICY::Type c) { return Iterator(c); }
00157
00159 typename POLICY::Head_type _f;
00160 };
00161
00162 }}
00163


```

## 16.185 I4/cxx/bits/smart\_ptr\_list.h File Reference


Implementation of a list of smart-pointer-managed objects.

```
#include "../type_traits"
```

Include dependency graph for smart\_ptr\_list.h:



This graph shows which files directly or indirectly include this file:



## Data Structures

- class `cxx::Bits::Smart_ptr_list_item< T, STORE_T >`  
*List item for an arbitrary item in a `Smart_ptr_list`.*
- class `cxx::Bits::Smart_ptr_list< ITEM >`  
*List of smart-pointer-managed objects.*

## Namespaces

- namespace `cxx`  
*Our C++ library.*
- namespace `cxx::Bits`  
*Internal helpers for the `cxx` package.*

## 16.185.1 Detailed Description

Implementation of a list of smart-pointer-managed objects.

Definition in file [smart\\_ptr\\_list.h](#).

## 16.186 smart\_ptr\_list.h

[Go to the documentation of this file.](#)

```

00001
00005 /*
00006  * Copyright (C) 2018, 2022, 2024 Kernkonzept GmbH.
00007  * Author(s): Sarah Hoffmann <sarah.hoffmann@kernkonzept.com>
00008  *
00009  * License: see LICENSE.spdx (in this directory or the directories above)
00010  */
00011 #pragma once
00012
00013 #include "../type_traits"
00014
00015 namespace cxx { namespace Bits {
00016

```

```

00026 template <typename T, typename STORE_T>
00027 class Smart_ptr_list_item
00028 {
00029     using Value_type = T;
00030     using Storage_type = STORE_T;
00031
00032     template<typename U> friend class Smart_ptr_list;
00033     Storage_type _n;
00034 };
00035
00045 template <typename ITEM>
00046 class Smart_ptr_list
00047 {
00048     using Value_type = typename ITEM::Value_type;
00049     using Next_type = typename ITEM::Storage_type;
00050
00051 public:
00052     class Iterator
00053     {
00054     public:
00055         Iterator() : _c(nullptr) {}
00056
00057         Value_type *operator * () const { return _c; }
00058         Value_type *operator -> () const { return _c; }
00059
00060         Iterator operator ++ ()
00061         {
00062             _c = _c->n.get();
00063             return *this;
00064         }
00065
00066         bool operator == (Iterator const &o) const { return _c == o._c; }
00067         bool operator != (Iterator const &o) const { return !operator == (o); }
00068
00069     private:
00070         friend class Smart_ptr_list;
00071
00072         explicit Iterator(Value_type *i) : _c(i) {}
00073
00074         Value_type *_c;
00075     };
00076
00077     class Const_iterator
00078     {
00079     public:
00080         Const_iterator() : _c(nullptr) {}
00081
00082         Value_type const *operator * () const { return _c; }
00083         Value_type const *operator -> () const { return _c; }
00084
00085         Const_iterator operator ++ ()
00086         {
00087             _c = _c->n.get();
00088             return *this;
00089         }
00090
00091         bool operator == (Const_iterator const &o) const { return _c == o._c; }
00092         bool operator != (Const_iterator const &o) const { return !operator == (o); }
00093
00094     private:
00095         friend class Smart_ptr_list;
00096
00097         explicit Const_iterator(Value_type const *i) : _c(i) {}
00098
00099         Value_type const *_c;
00100     };
00101
00102     Smart_ptr_list() : _b(&_f) {}
00103
00105     void push_front(Next_type &&e)
00106     {
00107         e->n = cxx::move(this->_f);
00108         this->_f = cxx::move(e);
00109
00110         if (_b == &_f)
00111             _b = &(_f->n);
00112     }
00113
00115     void push_front(Next_type const &e)
00116     {
00117         e->n = cxx::move(this->_f);
00118         this->_f = e;
00119
00120         if (_b == &_f)
00121             _b = &(_f->n);
00122     }
00123

```

```

00125 void push_back(Next_type &&e)
00126 {
00127     *_b = cxx::move(e);
00128     _b = &((*_b)->_n);
00129 }
00130
00132 void push_back(Next_type const &e)
00133 {
00134     *_b = e;
00135     _b = &((*_b)->_n);
00136 }
00137
00139 Value_type *front() const
00140 { return _f.get(); }
00141
00149 Next_type pop_front()
00150 {
00151     Next_type ret = cxx::move(_f);
00152
00153     if (ret)
00154         _f = cxx::move(ret->_n);
00155
00156     if (!_f)
00157         _b = &_f;
00158
00159     return ret;
00160 }
00161
00163 bool empty() const
00164 { return !_f; }
00165
00166 Iterator begin() { return Iterator(_f.get()); }
00167 Iterator end() { return Iterator(); }
00168
00169 Const_iterator begin() const { return Const_iterator(_f.get()); }
00170 Const_iterator end() const { return Const_iterator(); }
00171
00172 Const_iterator cbegin() const { return const_iterator(_f.get()); }
00173 Const_iterator cend() const { return Const_iterator(); }
00174
00175 private:
00176     Next_type _f;
00177     Next_type *_b;
00178 };
00179
00180 }

```

## 16.187 type\_traits.h

```

00001 // vi:ft=cpp
00002 /*
00003  * (c) 2008-2009 Alexander Warg <warg@os.inf.tu-dresden.de>,
00004  *      Torsten Frenzel <frenzel@os.inf.tu-dresden.de>
00005  *      economic rights: Technische Universität Dresden (Germany)
00006  *
00007  * License: see LICENSE.spdx (in this directory or the directories above)
00008  */
00009
00010 #pragma once
00011
00012 namespace cxx {
00013
00014     class Null_type;
00015
00016     template< bool flag, typename T, typename F >
00017     class Select
00018     {
00019     public:
00020         typedef T Type;
00021     };
00022
00023     template< typename T, typename F >
00024     class Select< false, T, F >
00025     {
00026     public:
00027         typedef F Type;
00028     };
00029
00030
00031
00032     template< typename T, typename U >
00033     class Conversion
00034     {

```

```

00035     typedef char S;
00036     class B { char dummy[2]; };
00037     static S test(U);
00038     static B test(...);
00039     static T make_T();
00040 public:
00041     enum
00042     {
00043         exists = sizeof(test(make_T())) == sizeof(S),
00044         two_way = exists && Conversion<U,T>::exists,
00045         exists_2_way = two_way,
00046         same_type = false
00047     };
00048 };
00049
00050 template< >
00051 class Conversion<void, void>
00052 {
00053 public:
00054     enum { exists = 1, two_way = 1, exists_2_way = two_way, same_type = 1 };
00055 };
00056
00057 template< typename T >
00058 class Conversion<T, T>
00059 {
00060 public:
00061     enum { exists = 1, two_way = 1, exists_2_way = two_way, same_type = 1 };
00062 };
00063
00064 template< typename T >
00065 class Conversion<void, T>
00066 {
00067 public:
00068     enum { exists = 0, two_way = 0, exists_2_way = two_way, same_type = 0 };
00069 };
00070
00071 template< typename T >
00072 class Conversion<T, void>
00073 {
00074 public:
00075     enum { exists = 0, two_way = 0, exists_2_way = two_way, same_type = 0 };
00076 };
00077
00078 template< int I >
00079 class Int_to_type
00080 {
00081 public:
00082     enum { i = I };
00083 };
00084
00085 namespace TT
00086 {
00087     template< typename U > class Pointer_traits
00088     {
00089     public:
00090         typedef Null_type Pointee;
00091         enum { value = false };
00092     };
00093
00094     template< typename U > class Pointer_traits< U* >
00095     {
00096     public:
00097         typedef U Pointee;
00098         enum { value = true };
00099     };
00100
00101     template< typename U > struct Ref_traits
00102     {
00103         enum { value = false };
00104         typedef U Referee;
00105     };
00106
00107     template< typename U > struct Ref_traits<U&>
00108     {
00109         enum { value = true };
00110         typedef U Referee;
00111     };
00112
00113
00114     template< typename U > struct Add_ref { typedef U &Type; };
00115     template< typename U > struct Add_ref<U&> { typedef U Type; };
00116
00117     template< typename U > struct PMF_traits { enum { value = false }; };
00118     template< typename U, typename F > struct PMF_traits<U F::*>
00119     { enum { value = true }; };
00120
00121

```

```

00122     template< typename U > class Is_unsigned { public: enum { value = false }; };
00123     template<> class Is_unsigned<unsigned> { public: enum { value = true }; };
00124     template<> class Is_unsigned<unsigned char> {
00125     public: enum { value = true };
00126     };
00127     template<> class Is_unsigned<unsigned short> {
00128     public: enum { value = true };
00129     };
00130     template<> class Is_unsigned<unsigned long> {
00131     public: enum { value = true };
00132     };
00133     template<> class Is_unsigned<unsigned long long> {
00134     public: enum { value = true };
00135     };
00136
00137     template< typename U > class Is_signed { public: enum { value = false }; };
00138     template<> class Is_signed<signed char> { public: enum { value = true }; };
00139     template<> class Is_signed<signed short> { public: enum { value = true }; };
00140     template<> class Is_signed<signed> { public: enum { value = true }; };
00141     template<> class Is_signed<signed long> { public: enum { value = true }; };
00142     template<> class Is_signed<signed long long> {
00143     public: enum { value = true };
00144     };
00145
00146     template< typename U > class Is_int { public: enum { value = false }; };
00147     template<> class Is_int< char > { public: enum { value = true }; };
00148     template<> class Is_int< bool > { public: enum { value = true }; };
00149     template<> class Is_int< wchar_t > { public: enum { value = true }; };
00150
00151     template< typename U > class Is_float { public: enum { value = false }; };
00152     template<> class Is_float< float > { public: enum { value = true }; };
00153     template<> class Is_float< double > { public: enum { value = true }; };
00154     template<> class Is_float< long double > { public: enum { value = true }; };
00155
00156     template<typename T> class Const_traits
00157     {
00158     public:
00159         enum { value = false };
00160         typedef T Type;
00161         typedef const T Const_type;
00162     };
00163
00164     template<typename T> class Const_traits<const T>
00165     {
00166     public:
00167         enum { value = true };
00168         typedef T Type;
00169         typedef const T Const_type;
00170     };
00171 };
00172
00173 template< typename T >
00174 class Type_traits
00175 {
00176 public:
00177     enum
00178     {
00179     {
00180         is_unsigned = TT::Is_unsigned<T>::value,
00181         is_signed   = TT::Is_signed<T>::value,
00182         is_int      = TT::Is_int<T>::value,
00183         is_float    = TT::Is_float<T>::value,
00184         is_pointer  = TT::Pointer_traits<T>::value,
00185         is_pointer_to_member = TT::PMF_traits<T>::value,
00186         is_reference = TT::Ref_traits<T>::value,
00187         is_scalar = is_unsigned || is_signed || is_int || is_pointer
00188             || is_pointer_to_member || is_reference,
00189         is_fundamental = is_unsigned || is_signed || is_float
00190             || Conversion<T, void>::same_type,
00191         is_const     = TT::Const_traits<T>::value,
00192
00193         alignment =
00194             (sizeof(T) >= sizeof(unsigned long)
00195              ? sizeof(unsigned long)
00196              : (sizeof(T) >= sizeof(unsigned)
00197               ? sizeof(unsigned)
00198               : (sizeof(T) >= sizeof(short)
00199                ? sizeof(short)
00200                : 1)))
00201     };
00202
00203     typedef typename Select<is_scalar, T, typename TT::Add_ref<typename
00204     TT::Const_traits<T>::Const_type>::Type>::Type Param_type;
00205     typedef typename TT::Pointer_traits<T>::Pointee Pointee_type;
00206     typedef typename TT::Ref_traits<T>::Referee Referee_type;
00207     typedef typename TT::Const_traits<T>::Type Non_const_type;
00208     typedef typename TT::Const_traits<T>::Const_type Const_type;

```

```

00208
00209     static unsigned long align(unsigned long a)
00210     {
00211         return (a + static_cast<unsigned long>(alignment) - 1UL)
00212             & ~(static_cast<unsigned long>(alignment) - 1UL);
00213     }
00214 };
00215
00216
00217 };
00218
00219
00220

```

## 16.188 dlist

```

00001 // vi:set ft=c++: -- Mode: C++ --
00002 /*
00003  * (c) 2011 Alexander Warg <warg@os.inf.tu-dresden.de>
00004  *     economic rights: Technische Universität Dresden (Germany)
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00008
00009 #pragma once
00010
00011 namespace cxx {
00012
00013     class D_list_item
00014     {
00015     public:
00016         constexpr D_list_item() : _dli_next(nullptr), _dli_prev(nullptr) {}
00017
00018         D_list_item(D_list_item const &) = delete;
00019         void operator = (D_list_item const &) = delete;
00020
00021     private:
00022         friend struct D_list_item_policy;
00023
00024         D_list_item *_dli_next, *_dli_prev;
00025     };
00026
00027     struct D_list_item_policy
00028     {
00029         typedef D_list_item Item;
00030         static D_list_item *prev(D_list_item *e) { return e->_dli_prev; }
00031         static D_list_item *next(D_list_item *e) { return e->_dli_next; }
00032         static D_list_item *prev(D_list_item const *e) { return e->_dli_prev; }
00033         static D_list_item *next(D_list_item const *e) { return e->_dli_next; }
00034     };
00035
00036     template< typename T >
00037     struct Sd_list_head_policy
00038     {
00039         typedef T *Head_type;
00040         static T *head(Head_type h) { return h; }
00041         static void set_head(Head_type &h, T *v) { h = v; }
00042     };
00043
00044     template<
00045         typename T,
00046         typename C = D_list_item_policy
00047     >
00048     class D_list_cyclic
00049     {
00050     protected:
00051         template< typename VALUE, typename ITEM >
00052         class __Iterator
00053         {
00054         public:
00055             typedef VALUE *Value_type;
00056             typedef VALUE *value_type;
00057
00058             __Iterator() {}
00059
00060             bool operator == (__Iterator const &o) const
00061             { return _c == o._c; }
00062
00063             bool operator != (__Iterator const &o) const
00064             { return _c != o._c; }
00065
00066             __Iterator &operator ++ ()
00067             {

```



```

00068     _c = C::next(_c);
00069     return *this;
00070 }
00071
00072 __Iterator &operator -- ()
00073 {
00074     _c = C::prev(_c);
00075     return *this;
00076 }
00077
00078 Value_type operator * () const { return static_cast<Value_type>(_c); }
00079 Value_type operator -> () const { return static_cast<Value_type>(_c); }
00080
00081 protected:
00082     friend class D_list_cyclic;
00083
00084     explicit __Iterator(ITEM *s) : _c(s) {}
00085
00086     ITEM *_c;
00087 };
00088
00089 public:
00090     typedef T *Value_type;
00091     typedef T *value_type;
00092     typedef __Iterator<T, typename C::Item> Iterator;
00093     typedef Iterator Const_iterator;
00094
00095     static void remove(T *e)
00096     {
00097         C::next(C::prev(e)) = C::next(e);
00098         C::prev(C::next(e)) = C::prev(e);
00099         C::next(e) = nullptr;
00100     }
00101
00102     static Iterator erase(Iterator const &e)
00103     {
00104         typename C::Item *n = C::next(*e);
00105         remove(*e);
00106         return __iter(n);
00107     }
00108
00109     static Iterator iter(T const *e) { return Iterator(const_cast<T*>(e)); }
00110
00111     static bool in_list(T const *e) { return C::next(const_cast<T*>(e)); }
00112     static bool has_sibling(T const *e) { return C::next(const_cast<T*>(e)) != e; }
00113
00114     static Iterator insert_after(T *e, Iterator const &pos)
00115     {
00116         C::prev(e) = pos._c;
00117         C::next(e) = C::next(pos._c);
00118         C::prev(C::next(pos._c)) = e;
00119         C::next(pos._c) = e;
00120         return pos;
00121     }
00122
00123     static Iterator insert_before(T *e, Iterator const &pos)
00124     {
00125         C::next(e) = pos._c;
00126         C::prev(e) = C::prev(pos._c);
00127         C::next(C::prev(pos._c)) = e;
00128         C::prev(pos._c) = e;
00129         return pos;
00130     }
00131
00132 protected:
00133     static void self_insert(typename C::Item *e)
00134     { C::next(e) = C::prev(e) = e; }
00135
00136     static void remove_last(T *e)
00137     { C::next(e) = nullptr; }
00138
00139     static void splice_heads(Const_iterator pos, typename C::Item *other_list)
00140     {
00141         typename C::Item *ins_next = pos._c;
00142         typename C::Item *ins_prev = C::prev(pos._c);
00143         typename C::Item *other_head = C::next(other_list);
00144         typename C::Item *other_tail = C::prev(other_list);
00145
00146         C::next(ins_prev) = other_head;
00147         C::prev(other_head) = ins_prev;
00148         C::prev(ins_next) = other_tail;
00149         C::next(other_tail) = ins_next;
00150     }
00151
00152     static Iterator __iter(typename C::Item *e) { return Iterator(e); }
00153 };
00154
00155
00156

```

```

00161 template<
00162     typename T,
00163     typename C = D_list_item_policy,
00164     typename H = Sd_list_head_policy<T>,
00165     bool BSS = false
00166 >
00167 class Sd_list : public D_list_cyclic<T, C>
00168 {
00169 private:
00170     typedef D_list_cyclic<T, C> Base;
00171 public:
00172     class Iterator : public Base::Iterator
00173     {
00174     public:
00175         Iterator &operator ++ ()
00176         {
00177             if (this->_c)
00178                 Base::Iterator::operator ++ ();
00179             if (this->_c == _h)
00180                 this->_c = nullptr;
00181             return *this;
00182         }
00183         Iterator &operator -- () = delete;
00184     private:
00185         friend class Sd_list;
00186         explicit Iterator(T *h) : Base::Iterator(h), _h(h) {}
00187         typename C::Item *_h;
00188     };
00189     class R_iterator : public Base::Iterator
00190     {
00191     public:
00192         R_iterator &operator ++ ()
00193         {
00194             if (this->_c)
00195                 Base::Iterator::operator -- ();
00196             if (this->_c == _h)
00197                 this->_c = nullptr;
00198             return *this;
00199         }
00200         R_iterator &operator -- () = delete;
00201     private:
00202         friend class Sd_list;
00203         explicit R_iterator(T *h) : Base::Iterator(h), _h(h) {}
00204         typename C::Item *_h;
00205     };
00206     //typedef typename Base::Iterator Iterator;
00207     enum Pos
00208     { Back, Front };
00209     Sd_list()
00210     {
00211         if (!BSS)
00212             H::set_head(_f, nullptr);
00213     }
00214     bool empty() const { return !H::head(_f); }
00215     T *front() const { return H::head(_f); }
00216     void remove(T *e)
00217     {
00218         T *h = H::head(_f);
00219         if (e == C::next(e)) // must be the last
00220         {
00221             Base::remove_last(e);
00222             H::set_head(_f, nullptr);
00223             return;
00224         }
00225         if (e == H::head(_f))
00226             H::set_head(_f, static_cast<T*>(C::next(h)));
00227         Base::remove(e);
00228     }
00229 }
00230

```

```

00248 Iterator erase(Iterator const &e)
00249 {
00250     Iterator next = e;
00251     ++next;
00252
00253     remove(*e);
00254     return next;
00255 }
00256
00257 void push(T *e, Pos pos)
00258 {
00259     T *h = H::head(_f);
00260     if (!h)
00261     {
00262         Base::self_insert(e);
00263         H::set_head(_f, e);
00264     }
00265     else
00266     {
00267         Base::insert_before(e, this->iter(h));
00268         if (pos == Front)
00269             H::set_head(_f, e);
00270     }
00271 }
00272
00273 void push_back(T *e) { push(e, Back); }
00274 void push_front(T *e) { push(e, Front); }
00275 void rotate_to(T *h) { H::set_head(_f, h); }
00276
00277 typename H::Head_type const &head() const { return _f; }
00278 typename H::Head_type &head() { return _f; }
00279
00280 Iterator begin() { return Iterator(H::head(_f)); }
00281 Iterator end() { return Iterator(nullptr); }
00282
00283 R_iterator rbegin()
00284 {
00285     if (head())
00286         return R_iterator(static_cast<T*>(C::prev(H::head(_f))));
00287     return R_iterator(nullptr);
00288 }
00289 R_iterator rend() { return R_iterator(nullptr); }
00290
00291 private:
00292     Sd_list(Sd_list const &);
00293     void operator = (Sd_list const &);
00294
00295     typename H::Head_type _f;
00296 };
00297
00298 template<
00299     typename T,
00300     typename C = D_list_item_policy,
00301     bool BSS = false
00302 >
00303 class D_list : public D_list_cyclic<T, C>
00304 {
00305 private:
00306     typedef D_list_cyclic<T, C> Base;
00307     typedef typename C::Item Internal_type;
00308
00309 public:
00310     enum Pos
00311     { Back, Front };
00312
00313     typedef typename Base::Iterator Iterator;
00314     typedef typename Base::Const_iterator Const_iterator;
00315     typedef T* value_type;
00316     typedef T* Value_type;
00317
00318     D_list() { this->self_insert(&_h); }
00319     ~D_list() { clear(); }
00320
00321     D_list(D_list &o)
00322     {
00323         if (o.empty())
00324         {
00325             this->self_insert(&_h);
00326         }
00327         else
00328         {
00329             Internal_type *p = C::prev(&o._h);
00330             Internal_type *n = C::next(&o._h);
00331             C::prev(&_h) = p;
00332             C::next(&_h) = n;
00333             C::next(p) = &_h;
00334             C::prev(n) = &_h;

```

```

00335         o.self_insert(&o._h);
00336     }
00337 }
00338
00339 D_list &operator=(D_list &&o)
00340 {
00341     if (&o == this)
00342         return *this;
00343
00344     clear();
00345
00346     if (!o.empty())
00347     {
00348         Internal_type *p = C::prev(&o._h);
00349         Internal_type *n = C::next(&o._h);
00350         C::prev(&_h) = p;
00351         C::next(&_h) = n;
00352         C::next(p) = &_h;
00353         C::prev(n) = &_h;
00354         o.self_insert(&o._h);
00355     }
00356 }
00357
00358 D_list(D_list const &) = delete;
00359 void operator = (D_list const &) = delete;
00360
00361 void splice(Const_iterator pos, D_list &&other)
00362 {
00363     if (other.empty())
00364         return;
00365
00366     Base::splice_heads(pos, &other._h);
00367     other.self_insert(&other._h);
00368 }
00369
00370 bool empty() const { return C::next(&_h) == &_h; }
00371
00372 static void remove(T *e) { Base::remove(e); }
00373 Iterator erase(Iterator const &e) { return Base::erase(e); }
00374
00375 void clear()
00376 {
00377     // Just clear the _dli_next pointers of all elements. It is the indicator
00378     // that an element is not on a list.
00379     Internal_type *i = C::next(&_h);
00380     while (i != &_h)
00381     {
00382         Internal_type *d = i;
00383         i = C::next(i);
00384         C::next(d) = nullptr;
00385     }
00386
00387     this->self_insert(&_h);
00388 }
00389
00390 void push(T *e, Pos pos)
00391 {
00392     if (pos == Front)
00393         Base::insert_after(e, end());
00394     else
00395         Base::insert_before(e, end());
00396 }
00397
00398 void push_back(T *e) { push(e, Back); }
00399 void push_front(T *e) { push(e, Front); }
00400
00401 T *pop_back()
00402 {
00403     T *ret = *(end()--);
00404     remove(ret);
00405     return ret;
00406 }
00407
00408 T *pop_front()
00409 {
00410     T *ret = *begin();
00411     remove(ret);
00412     return ret;
00413 }
00414
00415 Iterator begin() const { return this->__iter(C::next(const_cast<Internal_type *>(&_h))); }
00416 Iterator end() const { return this->__iter(const_cast<Internal_type *>(&_h)); }
00417
00418 bool has_sibling(T const *e)
00419 {
00420     return C::next(const_cast<T*>(e)) != &_h
00421         || C::prev(const_cast<T*>(e)) != &_h;
00422 }

```

```

00432     }
00433
00434 private:
00435     Internal_type _h;
00436 };
00437
00438 }
00439

```

## 16.189 elide\_dtor

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00002 /*
00003  * Copyright (C) 2026 Kernkonzept GmbH.
00004  * Author(s): Jan Klötzke <jan.kloetzke@kernkonzept.com>
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00008
00009 #pragma once
00010
00011 #include <l4/cxx/type_traits>
00012 #include <stddef.h>
00013
00014 namespace cxx {
00015
00027 template< typename T >
00028 class Elide_dtor
00029 {
00030 private:
00031     // Small helper struct so that we don't have to define a global operator new.
00032     struct X : T
00033     {
00034         constexpr void *operator new (size_t, void *p) noexcept { return p; }
00035         constexpr void operator delete (void *) {}
00036
00037         constexpr X() = default;
00038
00039         template<typename ...Args>
00040         constexpr X(Args && ...a) : T(cxx::forward<Args>(a)...) {}
00041
00042         constexpr X(T const &o) : T(o) {}
00043
00044         constexpr X(T &&o) : T(cxx::move(o)) {}
00045     };
00046
00047 public:
00048     template< typename ...Args >
00049     explicit constexpr Elide_dtor(Args && ...args)
00050     { new (_s) X(cxx::forward<Args>(args)...) };
00051
00052     explicit constexpr Elide_dtor(T const &o)
00053     { new (_s) X(o) };
00054
00055     explicit constexpr Elide_dtor(T &&o)
00056     { new (_s) X(cxx::move(o)) };
00057
00058     Elide_dtor(Elide_dtor const &) = delete;
00059     Elide_dtor(Elide_dtor &&) = delete;
00060
00061     ~Elide_dtor() = default;
00062
00063     T *operator -> () { return get(); }
00064     const T *operator -> () const { return get(); }
00065
00066     T *operator & () { return get(); }
00067     const T *operator & () const { return get(); }
00068
00069 private:
00070     T *get() { return reinterpret_cast<X*>(_s); }
00071     const T *get() const { return reinterpret_cast<X const*>(_s); }
00072
00073     alignas(X) char _s[sizeof(X)];
00074 };
00075
00076 }

```

Base exceptions.

```

graph TD
    libcxx_inceptions["libcxx/inceptions"] --> l4_cxx_l4types_h["l4/cxx/l4types.h"]
    libcxx_inceptions --> l4_cxx_basic_ostream["l4/cxx/basic_ostream"]
    libcxx_inceptions --> l4_cxx_backtrace_h["l4/cxx/backtrace.h"]
    libcxx_inceptions --> l4_sys_capability["l4/sys/capability"]
    libcxx_inceptions --> l4_sys_meta["l4/sys/meta"]
    libcxx_inceptions --> l4_sys_object["l4/sys/object"]
    libcxx_inceptions --> l4_sys_kernel_object_impl_h["l4sys/_kernel_object_impl.h"]
    libcxx_inceptions --> l4_sys_arch_ipc_h["l4sys/arch/ipc.h"]
    libcxx_inceptions --> l4_sys_arch_task_h["l4sys/arch/task.h"]
    libcxx_inceptions --> l4_sys_arch_utcb_h["l4sys/arch/utcb.h"]
    libcxx_inceptions --> l4_sys_compiler_h["l4sys/compiler.h"]
    libcxx_inceptions --> l4_sys_consts_h["l4sys/consts.h"]
    libcxx_inceptions --> l4_sys_farch_4limt_h["l4sys/farch/4limt.h"]
    libcxx_inceptions --> l4_sys_linkage_h["l4sys/linkage.h"]
    libcxx_inceptions --> l4_sys_timeout_h["l4sys/_timeout.h"]
    libcxx_inceptions --> l4_sys_types_h["l4sys/types.h"]
    libcxx_inceptions --> l4_sys_system_h["l4/system.h"]
    libcxx_inceptions --> l4_sys_ipc_array["ipc_array"]
    libcxx_inceptions --> l4_sys_ipc_iface["cxx/ipc_iface"]
    libcxx_inceptions --> l4_sys_ipc_basics["cxx/ipc_basics"]
    libcxx_inceptions --> l4_sys_ipc_types["l4sys/cxx/ipc_types"]
    libcxx_inceptions --> l4_sys_ipc_typeinfo_h["_typeinfo.h"]
    libcxx_inceptions --> l4_sys_ipc_capability_h["cxx/ipc_capability.h"]
    libcxx_inceptions --> l4_sys_ipc_task_h["l4sys/task.h"]
    libcxx_inceptions --> l4_sys_ipc_debug_h["l4sys/debug.h"]
    libcxx_inceptions --> l4_sys_ipc_pc_h["l4sys/pc.h"]
    libcxx_inceptions --> l4_sys_ipc_arch_ipc_h["l4sys/arch/ipc.h"]
    libcxx_inceptions --> l4_sys_ipc_arch_task_h["l4sys/arch/task.h"]
    libcxx_inceptions --> l4_sys_ipc_arch_utcb_h["l4sys/arch/utcb.h"]
    libcxx_inceptions --> l4_sys_ipc_compiler_h["l4sys/compiler.h"]
    libcxx_inceptions --> l4_sys_ipc_consts_h["l4sys/consts.h"]
    libcxx_inceptions --> l4_sys_ipc_farch_4limt_h["l4sys/farch/4limt.h"]
    libcxx_inceptions --> l4_sys_ipc_linkage_h["l4sys/linkage.h"]
    libcxx_inceptions --> l4_sys_ipc_timeout_h["l4sys/_timeout.h"]
    libcxx_inceptions --> l4_sys_ipc_types_h["l4sys/types.h"]
    libcxx_inceptions --> l4_sys_ipc_system_h["l4/system.h"]
    l4_cxx_l4types_h --> l4_sys_capability
    l4_cxx_l4types_h --> l4_sys_meta
    l4_cxx_l4types_h --> l4_sys_object
    l4_cxx_l4types_h --> l4_sys_kernel_object_impl_h
    l4_cxx_l4types_h --> l4_sys_arch_ipc_h
    l4_cxx_l4types_h --> l4_sys_arch_task_h
    l4_cxx_l4types_h --> l4_sys_arch_utcb_h
    l4_cxx_l4types_h --> l4_sys_compiler_h
    l4_cxx_l4types_h --> l4_sys_consts_h
    l4_cxx_l4types_h --> l4_sys_farch_4limt_h
    l4_cxx_l4types_h --> l4_sys_linkage_h
    l4_cxx_l4types_h --> l4_sys_timeout_h
    l4_cxx_l4types_h --> l4_sys_types_h
    l4_cxx_l4types_h --> l4_sys_system_h
    l4_cxx_l4types_h --> l4_sys_ipc_array
    l4_cxx_l4types_h --> l4_sys_ipc_iface
    l4_cxx_l4types_h --> l4_sys_ipc_basics
    l4_cxx_l4types_h --> l4_sys_ipc_types
    l4_cxx_l4types_h --> l4_sys_ipc_typeinfo_h
    l4_cxx_l4types_h --> l4_sys_ipc_capability_h
    l4_cxx_l4types_h --> l4_sys_ipc_task_h
    l4_cxx_l4types_h --> l4_sys_ipc_debug_h
    l4_cxx_l4types_h --> l4_sys_ipc_pc_h
    l4_cxx_l4types_h --> l4_sys_ipc_arch_ipc_h
    l4_cxx_l4types_h --> l4_sys_ipc_arch_task_h
    l4_cxx_l4types_h --> l4_sys_ipc_arch_utcb_h
    l4_cxx_l4types_h --> l4_sys_ipc_compiler_h
    l4_cxx_l4types_h --> l4_sys_ipc_consts_h
    l4_cxx_l4types_h --> l4_sys_ipc_farch_4limt_h
    l4_cxx_l4types_h --> l4_sys_ipc_linkage_h
    l4_cxx_l4types_h --> l4_sys_ipc_timeout_h
    l4_cxx_l4types_h --> l4_sys_ipc_types_h
    l4_cxx_l4types_h --> l4_sys_ipc_system_h
    l4_cxx_basic_ostream --> l4_sys_capability
    l4_cxx_basic_ostream --> l4_sys_meta
    l4_cxx_basic_ostream --> l4_sys_object
    l4_cxx_basic_ostream --> l4_sys_kernel_object_impl_h
    l4_cxx_basic_ostream --> l4_sys_arch_ipc_h
    l4_cxx_basic_ostream --> l4_sys_arch_task_h
    l4_cxx_basic_ostream --> l4_sys_arch_utcb_h
    l4_cxx_basic_ostream --> l4_sys_compiler_h
    l4_cxx_basic_ostream --> l4_sys_consts_h
    l4_cxx_basic_ostream --> l4_sys_farch_4limt_h
    l4_cxx_basic_ostream --> l4_sys_linkage_h
    l4_cxx_basic_ostream --> l4_sys_timeout_h
    l4_cxx_basic_ostream --> l4_sys_types_h
    l4_cxx_basic_ostream --> l4_sys_system_h
    l4_cxx_basic_ostream --> l4_sys_ipc_array
    l4_cxx_basic_ostream --> l4_sys_ipc_iface
    l4_cxx_basic_ostream --> l4_sys_ipc_basics
    l4_cxx_basic_ostream --> l4_sys_ipc_types
    l4_cxx_basic_ostream --> l4_sys_ipc_typeinfo_h
    l4_cxx_basic_ostream --> l4_sys_ipc_capability_h
    l4_cxx_basic_ostream --> l4_sys_ipc_task_h
    l4_cxx_basic_ostream --> l4_sys_ipc_debug_h
    l4_cxx_basic_ostream --> l4_sys_ipc_pc_h
    l4_cxx_basic_ostream --> l4_sys_ipc_arch_ipc_h
    l4_cxx_basic_ostream --> l4_sys_ipc_arch_task_h
    l4_cxx_basic_ostream --> l4_sys_ipc_arch_utcb_h
    l4_cxx_basic_ostream --> l4_sys_ipc_compiler_h
    l4_cxx_basic_ostream --> l4_sys_ipc_consts_h
    l4_cxx_basic_ostream --> l4_sys_ipc_farch_4limt_h
    l4_cxx_basic_ostream --> l4_sys_ipc_linkage_h
    l4_cxx_basic_ostream --> l4_sys_ipc_timeout_h
    l4_cxx_basic_ostream --> l4_sys_ipc_types_h
    l4_cxx_basic_ostream --> l4_sys_ipc_system_h
    l4_cxx_backtrace_h --> l4_sys_capability
    l4_cxx_backtrace_h --> l4_sys_meta
    l4_cxx_backtrace_h --> l4_sys_object
    l4_cxx_backtrace_h --> l4_sys_kernel_object_impl_h
    l4_cxx_backtrace_h --> l4_sys_arch_ipc_h
    l4_cxx_backtrace_h --> l4_sys_arch_task_h
    l4_cxx_backtrace_h --> l4_sys_arch_utcb_h
    l4_cxx_backtrace_h --> l4_sys_compiler_h
    l4_cxx_backtrace_h --> l4_sys_consts_h
    l4_cxx_backtrace_h --> l4_sys_farch_4limt_h
    l4_cxx_backtrace_h --> l4_sys_linkage_h
    l4_cxx_backtrace_h --> l4_sys_timeout_h
    l4_cxx_backtrace_h --> l4_sys_types_h
    l4_cxx_backtrace_h --> l4_sys_system_h
    l4_cxx_backtrace_h --> l4_sys_ipc_array
    l4_cxx_backtrace_h --> l4_sys_ipc_iface
    l4_cxx_backtrace_h --> l4_sys_ipc_basics
    l4_cxx_backtrace_h --> l4_sys_ipc_types
    l4_cxx_backtrace_h --> l4_sys_ipc_typeinfo_h
    l4_cxx_backtrace_h --> l4_sys_ipc_capability_h
    l4_cxx_backtrace_h --> l4_sys_ipc_task_h
    l4_cxx_backtrace_h --> l4_sys_ipc_debug_h
    l4_cxx_backtrace_h --> l4_sys_ipc_pc_h
    l4_cxx_backtrace_h --> l4_sys_ipc_arch_ipc_h
    l4_cxx_backtrace_h --> l4_sys_ipc_arch_task_h
    l4_cxx_backtrace_h --> l4_sys_ipc_arch_utcb_h
    l4_cxx_backtrace_h --> l4_sys_ipc_compiler_h
    l4_cxx_backtrace_h --> l4_sys_ipc_consts_h
    l4_cxx_backtrace_h --> l4_sys_ipc_farch_4limt_h
    l4_cxx_backtrace_h --> l4_sys_ipc_linkage_h
    l4_cxx_backtrace_h --> l4_sys_ipc_timeout_h
    l4_cxx_backtrace_h --> l4_sys_ipc_types_h
    l4_cxx_backtrace_h --> l4_sys_ipc_system_h
    l4_sys_capability --> l4_sys_meta
    l4_sys_capability --> l4_sys_object
    l4_sys_capability --> l4_sys_kernel_object_impl_h
    l4_sys_capability --> l4_sys_arch_ipc_h
    l4_sys_capability --> l4_sys_arch_task_h
    l4_sys_capability --> l4_sys_arch_utcb_h
    l4_sys_capability --> l4_sys_compiler_h
    l4_sys_capability --> l4_sys_consts_h
    l4_sys_capability --> l4_sys_farch_4limt_h
    l4_sys_capability --> l4_sys_linkage_h
    l4_sys_capability --> l4_sys_timeout_h
    l4_sys_capability --> l4_sys_types_h
    l4_sys_capability --> l4_sys_system_h
    l4_sys_capability --> l4_sys_ipc_array
    l4_sys_capability --> l4_sys_ipc_iface
    l4_sys_capability --> l4_sys_ipc_basics
    l4_sys_capability --> l4_sys_ipc_types
    l4_sys_capability --> l4_sys_ipc_typeinfo_h
    l4_sys_capability --> l4_sys_ipc_capability_h
    l4_sys_capability --> l4_sys_ipc_task_h
    l4_sys_capability --> l4_sys_ipc_debug_h
    l4_sys_capability --> l4_sys_ipc_pc_h
    l4_sys_capability --> l4_sys_ipc_arch_ipc_h
    l4_sys_capability --> l4_sys_ipc_arch_task_h
    l4_sys_capability --> l4_sys_ipc_arch_utcb_h
    l4_sys_capability --> l4_sys_ipc_compiler_h
    l4_sys_capability --> l4_sys_ipc_consts_h
    l4_sys_capability --> l4_sys_ipc_farch_4limt_h
    l4_sys_capability --> l4_sys_ipc_linkage_h
    l4_sys_capability --> l4_sys_ipc_timeout_h
    l4_sys_capability --> l4_sys_ipc_types_h
    l4_sys_capability --> l4_sys_ipc_system_h
    l4_sys_meta --> l4_sys_object
    l4_sys_meta --> l4_sys_kernel_object_impl_h
    l4_sys_meta --> l4_sys_arch_ipc_h
    l4_sys_meta --> l4_sys_arch_task_h
    l4_sys_meta --> l4_sys_arch_utcb_h
    l4_sys_meta --> l4_sys_compiler_h
    l4_sys_meta --> l4_sys_consts_h
    l4_sys_meta --> l4_sys_farch_4limt_h
    l4_sys_meta --> l4_sys_linkage_h
    l4_sys_meta --> l4_sys_timeout_h
    l4_sys_meta --> l4_sys_types_h
    l4_sys_meta --> l4_sys_system_h
    l4_sys_meta --> l4_sys_ipc_array
    l4_sys_meta --> l4_sys_ipc_iface
    l4_sys_meta --> l4_sys_ipc_basics
    l4_sys_meta --> l4_sys_ipc_types
    l4_sys_meta --> l4_sys_ipc_typeinfo_h
    l4_sys_meta --> l4_sys_ipc_capability_h
    l4_sys_meta --> l4_sys_ipc_task_h
    l4_sys_meta --> l4_sys_ipc_debug_h
    l4_sys_meta --> l4_sys_ipc_pc_h
    l4_sys_meta --> l4_sys_ipc_arch_ipc_h
    l4_sys_meta --> l4_sys_ipc_arch_task_h
    l4_sys_meta --> l4_sys_ipc_arch_utcb_h
    l4_sys_meta --> l4_sys_ipc_compiler_h
    l4_sys_meta --> l4_sys_ipc_consts_h
    l4_sys_meta --> l4_sys_ipc_farch_4limt_h
    l4_sys_meta --> l4_sys_ipc_linkage_h
    l4_sys_meta --> l4_sys_ipc_timeout_h
    l4_sys_meta --> l4_sys_ipc_types_h
    l4_sys_meta --> l4_sys_ipc_system_h
    l4_sys_object --> l4_sys_kernel_object_impl_h
    l4_sys_object --> l4_sys_arch_ipc_h
    l4_sys_object --> l4_sys_arch_task_h
    l4_sys_object --> l4_sys_arch_utcb_h
    l4_sys_object --> l4_sys_compiler_h
    l4_sys_object --> l4_sys_consts_h
    l4_sys_object --> l4_sys_farch_4limt_h
    l4_sys_object --> l4_sys_linkage_h
    l4_sys_object --> l4_sys_timeout_h
    l4_sys_object -->
```

- class `L4::Exception_tracer`  
*Back-trace support for exceptions.*
- class `L4::Base_exception`  
*Base class for all exceptions, thrown by the `L4Re` framework.*

- class [L4::Runtime\\_error](#)  
*Exception for an abstract runtime error.*
- class [L4::Out\\_of\\_memory](#)  
*Exception signalling insufficient memory.*
- class [L4::Element\\_already\\_exists](#)  
*Exception for duplicate element insertions.*
- class [L4::Unknown\\_error](#)  
*Exception for an unknown condition.*
- class [L4::Element\\_not\\_found](#)  
*Exception for a failed lookup (element not found).*
- class [L4::Invalid\\_capability](#)  
*Indicates that an invalid object was invoked.*
- class [L4::Com\\_error](#)  
*Error conditions during IPC.*
- class [L4::Bounds\\_error](#)  
*Access out of bounds.*

## Namespaces

- namespace [L4](#)  
*L4 low-level kernel interface.*

## Macros

- `#define L4_CXX_EXCEPTION_BACKTRACE 20`  
*Number of instruction pointers in backtrace.*

## 16.190.1 Detailed Description

Base exceptions.

Definition in file [exceptions](#).

## 16.191 exceptions

[Go to the documentation of this file.](#)

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00002 /*
00003  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00004  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00005  *      economic rights: Technische Universität Dresden (Germany)
00006  *
00007  * License: see LICENSE.spdx (in this directory or the directories above)
00008  */
00009 #pragma once
00010
00011 #include <l4/cxx/l4types.h>
00012 #include <l4/cxx/basic_ostream>
00013 #include <l4/sys/err.h>
00014 #include <l4/sys/capability>
00015
00016
00017 #ifndef L4_CXX_NO_EXCEPTION_BACKTRACE
00018 # define L4_CXX_EXCEPTION_BACKTRACE 20

```

```

00030 #endif
00031
00032 #if defined(L4_CXX_EXCEPTION_BACKTRACE)
00033 #include <l4/util/backtrace.h>
00034 #endif
00035
00037 namespace L4
00038 {
00051     class Exception_tracer
00052     {
00053     #if defined(L4_CXX_EXCEPTION_BACKTRACE)
00054     private:
00055         void *_pc_array[L4_CXX_EXCEPTION_BACKTRACE];
00056         int _frame_cnt;
00057
00058     protected:
00062     #if defined(__PIC__)
00063         Exception_tracer() noexcept : _frame_cnt(0) {}
00064     #else
00065         Exception_tracer() noexcept
00066         : _frame_cnt(l4util_backtrace(_pc_array, L4_CXX_EXCEPTION_BACKTRACE)) {}
00067     #endif
00068
00069     public:
00073         void const *const *pc_array() const noexcept { return _pc_array; }
00077         int frame_count() const noexcept { return _frame_cnt; }
00078     #else
00079     protected:
00083         Exception_tracer() noexcept {}
00084
00085     public:
00089         void const *const *pc_array() const noexcept { return 0; }
00093         int frame_count() const noexcept { return 0; }
00094     #endif
00095     };
00096
00105     class Base_exception : public Exception_tracer
00106     {
00107     protected:
00109         Base_exception() noexcept {}
00110
00111     public:
00115         virtual char const *str() const noexcept = 0;
00116
00118         virtual ~Base_exception() noexcept {}
00119     };
00120
00128     class Runtime_error : public Base_exception
00129     {
00130     private:
00131         long _errno;
00132         char _extra[80];
00133
00134     public:
00141         explicit Runtime_error(long err_no, char const *extra = 0) noexcept
00142         : _errno(err_no)
00143         {
00144             if (!extra)
00145                 _extra[0] = 0;
00146             else
00147             {
00148                 unsigned i = 0;
00149                 for (; i < sizeof(_extra) && extra[i]; ++i)
00150                     _extra[i] = extra[i];
00151                 _extra[i < sizeof(_extra) ? i : sizeof(_extra) - 1] = 0;
00152             }
00153         }
00154         char const *str() const noexcept override
00155         { return l4sys_errtostr(_errno); }
00156
00162         char const *extra_str() const { return _extra; }
00163         ~Runtime_error() noexcept {}
00164
00170         long err_no() const noexcept { return _errno; }
00171     };
00172
00177     class Out_of_memory : public Runtime_error
00178     {
00179     public:
00181         explicit Out_of_memory(char const *extra = "") noexcept
00182         : Runtime_error(-L4_ENOMEM, extra) {}
00184         ~Out_of_memory() noexcept {}
00185     };
00186
00187
00192     class Element_already_exists : public Runtime_error
00193     {

```



```

00194 public:
00195     explicit Element_already_exists(char const *e = "") noexcept
00196     : Runtime_error(-L4_EEXIST, e) {}
00197     ~Element_already_exists() noexcept {}
00198 };
00199
00200 class Unknown_error : public Base_exception
00201 {
00210 public:
00211     Unknown_error() noexcept {}
00212     char const *str() const noexcept override { return "unknown error"; }
00213     ~Unknown_error() noexcept {}
00214 };
00215
00220 class Element_not_found : public Runtime_error
00221 {
00222 public:
00223     explicit Element_not_found(char const *e = "") noexcept
00224     : Runtime_error(-L4_ENOENT, e) {}
00225 };
00226
00234 class Invalid_capability : public Base_exception
00235 {
00236 private:
00237     Cap<void> const _o;
00238
00239 public:
00244     explicit Invalid_capability(Cap<void> const &o) noexcept : _o(o) {}
00245     template< typename T>
00246     explicit Invalid_capability(Cap<T> const &o) noexcept : _o(o.cap()) {}
00247     char const *str() const noexcept override { return "invalid object"; }
00248
00253     Cap<void> const &cap() const noexcept { return _o; }
00254     ~Invalid_capability() noexcept {}
00255 };
00256
00263 class Com_error : public Runtime_error
00264 {
00265 public:
00270     explicit Com_error(long err) noexcept : Runtime_error(err) {}
00271
00272     ~Com_error() noexcept {}
00273 };
00274
00278 class Bounds_error : public Runtime_error
00279 {
00280 public:
00281     explicit Bounds_error(char const *e = "") noexcept
00282     : Runtime_error(-L4_ERANGE, e) {}
00283     ~Bounds_error() noexcept {}
00284 };
00286 };
00287
00288 inline
00289 L4::BasicOStream &
00290 operator << (L4::BasicOStream &o, L4::Base_exception const &e)
00291 {
00292     o << "Exception: " << e.str() << ".\n";
00293     if (e.frame_count())
00294     {
00295         o << "Backtrace:\n";
00296         for (int i = 0; i < e.frame_count(); ++i)
00297             o << "    " << L4::n_hex(l4_addr_t(e.pc_array()[i])) << '\n';
00298     }
00299
00300     return o;
00301 }
00302
00303 inline
00304 L4::BasicOStream &
00305 operator << (L4::BasicOStream &o, L4::Runtime_error const &e)
00306 {
00307     o << "Exception: " << e.str();
00308     if (e.extra_str() && e.extra_str()[0])
00309         o << ": " << e.extra_str();
00310     o << ".\n";
00311     if (e.frame_count())
00312     {
00313         o << "Backtrace:\n";
00314         for (int i = 0; i < e.frame_count(); ++i)
00315             o << "    " << L4::n_hex(l4_addr_t(e.pc_array()[i])) << '\n';
00316     }
00317
00318     return o;
00319 }

```

## 16.192 hlist

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00002 /*
00003  * (c) 2011 Alexander Warg <warg@os.inf.tu-dresden.de>
00004  *     economic rights: Technische Universität Dresden (Germany)
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00008
00009 #pragma once
00010
00011 #include "bits/list_basics.h"
00012 #include "type_traits"
00013
00014 namespace cxx {
00015
00021 template<typename ELEM_TYPE>
00022 class H_list_item_t
00023 {
00024 public:
00030   H_list_item_t() : _n(0), _pn(0) {}
00037   ~H_list_item_t() noexcept { l_remove(); }
00038
00039 private:
00040   H_list_item_t(H_list_item_t const &) = delete;
00041
00042   template<typename T, typename P> friend class H_list;
00043   template<typename T, typename X> friend struct Bits::Basic_list_policy;
00044
00045   void l_remove() noexcept
00046   {
00047       if (!_pn)
00048           return;
00049
00050       *_pn = _n;
00051       if (_n)
00052           _n->_pn = _pn;
00053
00054       _pn = nullptr;
00055   }
00056
00057   H_list_item_t *_n, **_pn;
00058 };
00059
00061 typedef H_list_item_t<void> H_list_item;
00062
00068 template< typename T, typename POLICY = Bits::Basic_list_policy< T, H_list_item> >
00069 class H_list : public Bits::Basic_list<POLICY>
00070 {
00071 private:
00072     typedef typename POLICY::Item_type Item;
00073     typedef Bits::Basic_list<POLICY> Base;
00074     H_list(H_list const &);
00075     void operator = (H_list const &);
00076
00077 public:
00078     typedef typename Base::Iterator Iterator;
00079
00080     // BSS allocation
00081     explicit H_list(bool x) : Base(x) {}
00082     H_list() : Base() {}
00083
00093     static Iterator iter(T *c) { return Base::__iter(c->Item::_pn); }
00094
00096     static bool in_list(T const *e) { return e->Item::_pn; }
00097
00099     void add(T *e)
00100     {
00101         if (this->_f)
00102             this->_f->_pn = &e->Item::_n;
00103         e->Item::_n = this->_f;
00104         e->Item::_pn = &this->_f;
00105         this->_f = static_cast<Item*>(e);
00106     }
00107
00109     void push_front(T *e) { add(e); }
00110
00116     T *pop_front()
00117     {
00118         T *r = this->front();
00119         remove(r);
00120         return r;
00121     }
00122
00133     Iterator insert(T *e, Iterator const &pred)

```

```

00134 {
00135     Item **x = &this->_f;
00136     if (pred != Base::end())
00137         x = &(*pred)->_n;
00138
00139     e->Item::_n = *x;
00140
00141     if (*x)
00142         (*x)->_pn = &(e->Item::_n);
00143
00144     e->Item::_pn = x;
00145     *x = static_cast<Item*>(e);
00146     return iter(e);
00147 }
00148
00160 static Iterator insert_after(T *e, Iterator const &pred)
00161 {
00162     Item **x = &(*pred)->_n;
00163     e->Item::_n = *x;
00164
00165     if (*x)
00166         (*x)->_pn = &(e->Item::_n);
00167
00168     e->Item::_pn = x;
00169     *x = static_cast<Item*>(e);
00170     return iter(e);
00171 }
00172
00180 static void insert_before(T *e, Iterator const &succ)
00181 {
00182     Item **x = Base::__get_internal(succ);
00183
00184     e->Item::_n = *x;
00185     e->Item::_pn = x;
00186
00187     if (*x)
00188         (*x)->_pn = &e->Item::_n;
00189
00190     *x = static_cast<Item*>(e);
00191 }
00192
00204 static void replace(T *p, T *e)
00205 {
00206     e->Item::_n = p->Item::_n;
00207     e->Item::_pn = p->Item::_pn;
00208     *(p->Item::_pn) = static_cast<Item*>(e);
00209     if (e->Item::_n)
00210         e->Item::_n->_pn = &(e->Item::_n);
00211
00212     p->Item::_pn = nullptr;
00213 }
00214
00220 static void remove(T *e)
00221 { e->Item::l_remove(); }
00222
00236 static Iterator erase(Iterator const &e)
00237 { e->Item::l_remove(); return e; }
00238 };
00239
00247 template< typename T >
00248 struct H_list_t : H_list<T, Bits::Basic_list_policy< T, H_list_item_t<T> > >
00249 {
00250     H_list_t() = default;
00251     H_list_t(bool b)
00252         : H_list<T, Bits::Basic_list_policy< T, H_list_item_t<T> > >(b)
00253     {};
00254 };
00255
00256 template< typename T >
00257 class H_list_bss : public H_list<T>
00258 {
00259 public:
00260     H_list_bss() : H_list<T>(true) {}
00261 };
00262
00263 template< typename T >
00264 class H_list_t_bss : public H_list_t<T>
00265 {
00266 public:
00267     H_list_t_bss() : H_list_t<T>(true) {}
00268 };
00269
00270
00271 }


```

## 16.193 l4/cxx/iostream File Reference

IO Stream.

```
#include <l4/cxx/basic_ostream>
```

Include dependency graph for iostream:



### Namespaces

- namespace [L4](#)  
*L4 low-level kernel interface.*

### Variables

- BasicOStream **L4::cout**  
*Standard output stream.*
- BasicOStream **L4::cerr**  
*Standard error stream.*

### 16.193.1 Detailed Description

IO Stream.

Definition in file [iostream](#).

## 16.194 iostream

[Go to the documentation of this file.](#)

```
00001 // -*- Mode: C++ -*-
00002 // vim:ft=cpp
00003 /*
00004  * (c) 2004-2009 Alexander Warg <warg@os.inf.tu-dresden.de>,
00005  *                      Torsten Frenzel <frenzel@os.inf.tu-dresden.de>
00006  *      economic rights: Technische Universität Dresden (Germany)
00007  *
00008  * License: see LICENSE.spdx (in this directory or the directories above)
00009  */
00010 #pragma once
```

```
00015
00016 #include <l4/cxx/basic_ostream>
00017
00018 namespace L4 {
00019
00023     extern BasicOStream cout;
00024
00028     extern BasicOStream cerr;
00029
00030     extern void iostream_init();
00031
00032     static void __attribute__((used, constructor)) __iostream_init()
00033     { iostream_init(); }
00034 };
```

## 16.195.1 Detailed Description

IPC helper.

Definition in file [ipc\\_helper](#).

## 16.196 ipc\_helper

[Go to the documentation of this file.](#)

```
00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00002 /*
00003  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00004  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00005  *      economic rights: Technische Universität Dresden (Germany)
00006  *
00007  * License: see LICENSE.spdx (in this directory or the directories above)
00008  */
00009 #pragma once
00010
00011 #include <l4/cxx/exceptions>
00012 #include <l4/sys/utcb.h>
00013
00014 namespace L4
00015 {
00016 #ifdef __EXCEPTIONS
00017     inline void
00018     throw_ipc_exception([[maybe_unused]] L4::Cap<void> const &o,
00019                         l4_msgtag_t const &err, l4_utcb_t *utcb)
00019     {
00020         if (err.has_error())
00021             throw (L4::Com_error(l4_error_u(err, utcb)));
00022     }
00023
00024     inline void
00025     throw_ipc_exception(void const *o, l4_msgtag_t const &err,
00026                         l4_utcb_t *utcb)
00027     { throw_ipc_exception(L4::Cap<void>(o), err, utcb); }
00028 #endif
00029 }
```

## 16.197 l4/cxx/ipc\_stream File Reference

IPC stream.

```
#include <l4/sys/ipc.h>
#include <l4/sys/capability>
#include <l4/sys/cxx/ipc_types>
#include <l4/sys/cxx/ipc_varg>
#include <l4/cxx/type_traits>
#include <l4/cxx/minmax>
```



## Namespaces

- namespace [L4](#)  
*L4 low-level kernel interface.*
- namespace [L4::lpc](#)  
*IPC related functionality.*

## Functions

- `template<typename T>`  
`Internal::Buf_cp_out< T > L4::lpc::buf\_cp\_out (T const *v, unsigned long size)`  
*Insert an array into an [lpc::Ostream](#).*
- `template<typename T>`  
`Internal::Buf_cp_in< T > L4::lpc::buf\_cp\_in (T *v, unsigned long &size)`  
*Extract an array from an [lpc::Istream](#).*
- `template<typename T>`  
`Str_cp_in< T > L4::lpc::str\_cp\_in (T *v, unsigned long &size)`  
*Create a [Str\\_cp\\_in](#) for the given values.*
- `template<typename T>`  
`Msg_ptr< T > L4::lpc::msg\_ptr (T *&p)`  
*Create an [Msg\\_ptr](#) to adjust the given pointer.*
- `template<typename T>`  
`Internal::Buf_in< T > L4::lpc::buf\_in (T *&v, unsigned long &size)`  
*Return a pointer to stream array data.*
- `L4::lpc::Istream & operator>> (L4::lpc::Istream &s, bool &v)`  
*Extract one element of type *T* from the stream *s*.*
- `L4::lpc::Istream & operator>> (L4::lpc::Istream &s, l4\_msgtag\_t &v)`  
*Extract the *L4* message tag from the stream *s*.*
- `template<typename T>`  
`L4::lpc::Istream & operator>> (L4::lpc::Istream &s, L4::lpc::Internal::Buf\_in< T > const &v)`  
*Extract an array of *T* elements from the stream *s*.*
- `template<typename T>`  
`L4::lpc::Istream & operator>> (L4::lpc::Istream &s, L4::lpc::Msg\_ptr< T > const &v)`  
*Extract an element of type *T* from the stream *s*.*
- `template<typename T>`  
`L4::lpc::Istream & operator>> (L4::lpc::Istream &s, L4::lpc::Str\_cp\_in< T > const &v)`  
*Extract a zero-terminated string from the stream.*
- `L4::lpc::Ostream & operator<< (L4::lpc::Ostream &s, bool v)`  
*Insert an element to type *T* into the stream *s*.*
- `L4::lpc::Ostream & operator<< (L4::lpc::Ostream &s, l4\_msgtag\_t const &v)`  
*Insert the *L4* message tag into the stream *s*.*
- `template<typename T>`  
`L4::lpc::Ostream & operator<< (L4::lpc::Ostream &s, L4::lpc::Internal::Buf\_cp\_out< T > const &v)`  
*Insert an array with elements of type *T* into the stream *s*.*
- `L4::lpc::Ostream & operator<< (L4::lpc::Ostream &s, char const *v)`  
*Insert a zero terminated character string into the stream *s*.*
- `template<typename T>`  
`T L4::lpc::read (Istream &s)`  
*Read a value out of a stream.*



## 16.197.1 Detailed Description

IPC stream.

Definition in file [ipc\\_stream](#).

## 16.197.2 Function Documentation

### 16.197.2.1 `operator<<()` [1/4]

```
L4::Ipc::Ostream & operator<< (  
    L4::Ipc::Ostream & s,  
    bool v) [inline]
```

Insert an element to type `T` into the stream `s`.

#### Parameters

<code>s</code>	The stream to insert the element <code>v</code> .
<code>v</code>	The element to insert.

#### Returns

The stream `s`.

Definition at line [1197](#) of file [ipc\\_stream](#).

References [L4::Ipc::Ostream::put\(\)](#).

Here is the call graph for this function:



**16.197.2.2 operator<<() [2/4]**

```
L4::Ipc::Ostream & operator<< (
    L4::Ipc::Ostream & s,
    char const * v) [inline]
```

Insert a zero terminated character string into the stream *s*.

**Parameters**

<i>s</i>	The stream to insert the string <i>v</i> .
<i>v</i>	The string to insert.

**Returns**

The stream *s*.

This operator produces basically the same content as the array insertion, however the length of the array is calculated using `strlen(v) + 1`. The string is copied into the message including the trailing zero.

Definition at line 1269 of file `ipc_stream`.

References `L4::Ipc::Ostream::put()`.

Here is the call graph for this function:

**16.197.2.3 operator<<() [3/4]**

```
template<typename T>
L4::Ipc::Ostream & operator<< (
    L4::Ipc::Ostream & s,
    L4::Ipc::Internal::Buf_cp_out< T > const & v) [inline]
```

Insert an array with elements of type *T* into the stream *s*.

**Parameters**

<i>s</i>	The stream to insert the array <i>v</i> .
<i>v</i>	The array to insert (see <code>Ipc::Buf_cp_out()</code> ).

**Returns**

The stream *s*.

Definition at line 1248 of file [ipc\\_stream](#).

References [L4::ipc::Ostream::put\(\)](#).

Here is the call graph for this function:

**16.197.2.4 operator<<() [4/4]**

```
L4::Ipc::Ostream & operator<< (  
    L4::Ipc::Ostream & s,  
    l4_msgtag_t const & v) [inline]
```

Insert the [L4](#) message tag into the stream *s*.

**Parameters**

<i>s</i>	The stream to insert the tag <i>v</i> .
<i>v</i>	The <a href="#">L4</a> message tag to insert.

**Returns**

The stream *s*.

**Note**

Only one message tag can be inserted into a stream. Multiple insertions simply overwrite previous insertions.

Definition at line 1232 of file [ipc\\_stream](#).

References [L4::ipc::Ostream::tag\(\)](#).

Here is the call graph for this function:



**16.197.2.5 operator>>() [1/6]**

```
L4::Ipc::Istream & operator>> (
    L4::Ipc::Istream & s,
    bool & v) [inline]
```

Extract one element of type T from the stream s.

**Parameters**

	s	The stream to extract from.
out	v	Extracted value.


**Returns**

The stream s.

Definition at line 1044 of file [ipc\\_stream](#).

References [L4::Ipc::Istream::get\(\)](#).

Here is the call graph for this function:

**16.197.2.6 operator>>>() [2/6]**

```
template<typename T>
L4::Ipc::Istream & operator>>> (
    L4::Ipc::Istream & s,
    L4::Ipc::Internal::Buf_cp_in< T > const & v) [inline]
```

Extract an array of T elements from the stream s.

**Parameters**

	s	The stream to extract from.
out	v	<a href="#">Buffer</a> description to copy the array to (Ipc::Buf_cp_out()).

**Returns**

The stream *s*.


This operator does a copy out of the data into the given buffer.

See `lpc::Buf_in`, `lpc::Buf_cp_in`, and `lpc::Buf_cp_out`.

Definition at line 1151 of file `ipc_stream`.

References `L4::lpc::Istream::get()`.

Here is the call graph for this function:

**16.197.2.7 operator>>() [3/6]**

```

template<typename T>
L4::Ipc::Istream & operator>> (
    L4::Ipc::Istream & s,
    L4::Ipc::Internal::Buf_in< T > const & v) [inline]
  
```

Extract an array of *T* elements from the stream *s*.

**Parameters**

	<i>s</i>	The stream to extract from.
out	<i>v</i>	Pointer to the extracted array ( <code>ipc_buf_in()</code> ).

**Returns**

The stream *s*.

This operator actually does not copy out the data in the array, but returns a pointer into the message buffer itself. This means that the data is only valid as long as there is no new data inserted into the stream.

**Note**


If array does not fit into transmitted words size will be set to zero. Client has to implement check against zero.

See `lpc::Buf_in`, `lpc::Buf_cp_in`, and `lpc::Buf_cp_out`.

Definition at line 1103 of file `ipc_stream`.

References `L4::lpc::Istream::get()`, and `L4::lpc::Istream::has_more()`.

Here is the call graph for this function:

**16.197.2.8 operator>>() [4/6]**

```

template<typename T>
L4::Ipc::Istream & operator>> (
    L4::Ipc::Istream & s,
    L4::Ipc::Msg_ptr< T > const & v) [inline]
  
```

Extract an element of type `T` from the stream `s`.

**Parameters**

	<code>s</code>	The stream to extract from.
<code>out</code>	<code>v</code>	Pointer to the extracted element.

**Returns**

The stream `s`.


This operator actually does not copy out the data, but returns a pointer into the message buffer itself. This means that the data is only valid as long as there is no new data inserted into the stream.

See `Msg_ptr`.

Definition at line 1130 of file `ipc_stream`.

References `L4::lpc::Istream::get()`.

Here is the call graph for this function:



**16.197.2.9 operator>>() [5/6]**

```
template<typename T>
L4::Ipc::Istream & operator>> (
    L4::Ipc::Istream & s,
    L4::Ipc::Str_cp_in< T > const & v) [inline]
```

Extract a zero-terminated string from the stream.

**Parameters**

	<i>s</i>	The stream to extract from.
out	<i>v</i>	Buffer description to copy the array to (lpc::Str_cp_out()).

**Returns**


The stream *s*.

This operator does a copy out of the data into the given buffer.

Definition at line 1172 of file `lpc_stream`.

References `L4::lpc::Istream::get()`.

Here is the call graph for this function:

**16.197.2.10 operator>>() [6/6]**

```
L4::Ipc::Istream & operator>> (
    L4::Ipc::Istream & s,
    l4_msgtag_t & v) [inline]
```

Extract the `L4` message tag from the stream *s*.

**Parameters**

	<i>s</i>	The stream to extract from.
out	<i>v</i>	The extracted tag.

**Returns**

The stream `s`.

Definition at line 1078 of file `ipc_stream`.

References `L4::lpc::lstream::tag()`.

Here is the call graph for this function:



## 16.198 ipc\_stream

[Go to the documentation of this file.](#)

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00006 /*
00007  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00008  *               Alexander Warg <warg@os.inf.tu-dresden.de>,
00009  *               Torsten Frenzel <frenzel@os.inf.tu-dresden.de>
00010  *               economic rights: Technische Universität Dresden (Germany)
00011  *
00012  * License: see LICENSE.spdx (in this directory or the directories above)
00013  */
00014 #pragma once
00015
00016 #include <l4/sys/ipc.h>
00017 #include <l4/sys/capability>
00018 #include <l4/sys/cxx/ipc_types>
00019 #include <l4/sys/cxx/ipc_varg>
00020 #include <l4/cxx/type_traits>
00021 #include <l4/cxx/minmax>
00022
00023 namespace L4 {
00024 namespace lpc {
00025
00026 class ostream;
00027 class istream;
00028
00029 namespace internal {
00047 template< typename T >
00048 class buf_cp_out
00049 {
00050 public:
00057   buf_cp_out(T const *v, unsigned long size) : _v(v), _s(size) {}
00058
00066   unsigned long size() const { return _s; }
00067
00075   T const *buf() const { return _v; }
00076
00077 private:
00078   friend class ostream;
00079   T const *_v;
00080   unsigned long _s;
00081 };
00082 }
00083
00099 template< typename T >
00100 internal::buf_cp_out<T> buf_cp_out(T const *v, unsigned long size)
00101 { return internal::buf_cp_out<T>(v, size); }
00102
00103
00104 namespace internal {
  
```



```

00117 template< typename T >
00118 class Buf_cp_in
00119 {
00120 public:
00129   Buf_cp_in(T *v, unsigned long &size) : _v(v), _s(&size) {}
00130
00131   unsigned long &size() const { return *_s; }
00132   T *buf() const { return _v; }
00133
00134 private:
00135   friend class Istream;
00136   T *_v;
00137   unsigned long *_s;
00138 };
00139 }
00140
00158 template< typename T >
00159 Internal::Buf_cp_in<T> buf_cp_in(T *v, unsigned long &size)
00160 { return Internal::Buf_cp_in<T>(v, size); }
00161
00177 template< typename T >
00178 class Str_cp_in
00179 {
00180 public:
00189   Str_cp_in(T *v, unsigned long &size) : _v(v), _s(&size) {}
00190
00191   unsigned long &size() const { return *_s; }
00192   T *buf() const { return _v; }
00193
00194 private:
00195   friend class Istream;
00196   T *_v;
00197   unsigned long *_s;
00198 };
00199
00212 template< typename T >
00213 Str_cp_in<T> str_cp_in(T *v, unsigned long &size)
00214 { return Str_cp_in<T>(v, size); }
00215
00228 template< typename T >
00229 class Msg_ptr
00230 {
00231 private:
00232   T **_p;
00233 public:
00240   explicit Msg_ptr(T *&p) : _p(&p) {}
00241   void set(T *p) const { *_p = p; }
00242 };
00243
00251 template< typename T >
00252 Msg_ptr<T> msg_ptr(T *&p)
00253 { return Msg_ptr<T>(p); }
00254
00255 namespace Internal {
00270 template< typename T >
00271 class Buf_in
00272 {
00273 public:
00280   Buf_in(T *&v, unsigned long &size) : _v(&v), _s(&size) {}
00281
00282   void set_size(unsigned long s) const { *_s = s; }
00283   T *&buf() const { return *_v; }
00284
00285 private:
00286   friend class Istream;
00287   T **_v;
00288   unsigned long *_s;
00289 };
00290 }
00291
00309 template< typename T >
00310 Internal::Buf_in<T> buf_in(T *&v, unsigned long &size)
00311 { return Internal::Buf_in<T>(v, size); }
00312
00313 namespace Utcbl_stream_check
00314 {
00315   static bool check_utcb_data_offset(unsigned sz)
00316   { return sz > sizeof(l4_umword_t) * L4_UTCB_GENERIC_DATA_SIZE; }
00317 }
00318
00319
00334 class Istream
00335 {
00336 public:
00348   Istream(l4_utcb_t *utcb)
00349   : _tag(), _utcb(utcb),

```

```

00350     _current_msg(reinterpret_cast<char*>(l4_utcb_mr_u(utcb)->mr)),
00351     _pos(0), _current_buf(0)
00352 {}
00353
00358 void reset()
00359 {
00360     _pos = 0;
00361     _current_buf = 0;
00362     _current_msg = reinterpret_cast<char*>(l4_utcb_mr_u(utcb)->mr);
00363 }
00364
00368 template< typename T >
00369 bool has_more(unsigned long count = 1)
00370 {
00371     auto const max_bytes = L4_UTCB_GENERIC_DATA_SIZE * sizeof(l4_umword_t);
00372     unsigned apos = cxx::Type_traits<T>::align(_pos);
00373     return (count <= max_bytes / sizeof(T))
00374         && (apos + (sizeof(T) * count)
00375             <= _tag.words() * sizeof(l4_umword_t));
00376 }
00377
00382
00393 template< typename T >
00394 unsigned long get(T *buf, unsigned long elems)
00395 {
00396     if (L4_UNLIKELY(!has_more<T>(elems)))
00397         return 0;
00398
00399     unsigned long size = elems * sizeof(T);
00400     _pos = cxx::Type_traits<T>::align(_pos);
00401
00402     __builtin_memcpy(buf, _current_msg + _pos, size);
00403     _pos += size;
00404     return elems;
00405 }
00406
00407
00413 template< typename T >
00414 void skip(unsigned long elems)
00415 {
00416     if (L4_UNLIKELY(!has_more<T>(elems)))
00417         return;
00418
00419     unsigned long size = elems * sizeof(T);
00420     _pos = cxx::Type_traits<T>::align(_pos);
00421     _pos += size;
00422 }
00423
00438 template< typename T >
00439 unsigned long get(Msg_ptr<T> const &buf, unsigned long elems = 1)
00440 {
00441     if (L4_UNLIKELY(!has_more<T>(elems)))
00442         return 0;
00443
00444     unsigned long size = elems * sizeof(T);
00445     _pos = cxx::Type_traits<T>::align(_pos);
00446
00447     buf.set(reinterpret_cast<T*>(_current_msg + _pos));
00448     _pos += size;
00449     return elems;
00450 }
00451
00452
00463 template< typename T >
00464 bool get(T &v)
00465 {
00466     if (L4_UNLIKELY(!has_more<T>()))
00467     {
00468         v = T();
00469         return false;
00470     }
00471
00472     _pos = cxx::Type_traits<T>::align(_pos);
00473     v = *(reinterpret_cast<T*>(_current_msg + _pos));
00474     _pos += sizeof(T);
00475     return true;
00476 }
00477
00478
00479 bool get(Ipc::Varg *va)
00480 {
00481     Ipc::Varg::Tag t;
00482     if (!has_more<Ipc::Varg::Tag>())
00483     {
00484         va->tag(0);
00485         return 0;
00486     }

```

```

00487     get(t);
00488     va->tag(t);
00489     char const *d;
00490     get(msg_ptr(d), va->length());
00491     va->data(d);
00492
00493     return 1;
00494 }
00495
00505 l4_msgtag_t tag() const { return _tag; }
00506
00507
00517 l4_msgtag_t &tag() { return _tag; }
00518
00520
00525 inline bool put(Rcv_fpage const &);
00526
00531 inline bool put(Small_buf const &);
00532
00533
00538
00548 inline l4_msgtag_t wait(l4_umword_t *src)
00549 { return wait(src, L4_IPC_NEVER); }
00550
00561 inline l4_msgtag_t wait(l4_umword_t *src, l4_timeout_t timeout);
00562
00572 inline l4_msgtag_t receive(l4_cap_idx_t src)
00573 { return receive(src, L4_IPC_NEVER); }
00574
00575 inline l4_msgtag_t receive(l4_cap_idx_t src, l4_timeout_t timeout);
00576
00577
00581 inline l4_utcb_t *utcb() const { return _utcb; }
00582
00583 protected:
00584     l4_msgtag_t _tag;
00585     l4_utcb_t *_utcb;
00586     char *_current_msg;
00587     unsigned _pos;
00588     unsigned char _current_buf;
00589 };
00590
00591 class Istream_copy : public Istream
00592 {
00593 private:
00594     l4_msg_regs_t _mrs;
00595
00596 public:
00597     Istream_copy(Istream const &o) : Istream(o), _mrs(*l4_utcb_mr_u(o.utcb()))
00598     {
00599         // do some reverse mr to utcb trickery
00600         _utcb = reinterpret_cast<l4_utcb_t *>
00601             (reinterpret_cast<l4_addr_t>(&_mrs)
00602              - reinterpret_cast<l4_addr_t>(l4_utcb_mr_u(nullptr)));
00603         _current_msg = reinterpret_cast<char*>(l4_utcb_mr_u(_utcb)->mr);
00604     }
00605
00606 };
00607
00623 class Ostream
00624 {
00625 public:
00629     Ostream(l4_utcb_t *utcb)
00630     : _tag(), _utcb(utcb),
00631       _current_msg(reinterpret_cast<char *>(l4_utcb_mr_u(_utcb)->mr)),
00632       _pos(0), _current_item(0)
00633     {}
00634
00638     void reset()
00639     {
00640         _pos = 0;
00641         _current_item = 0;
00642         _current_msg = reinterpret_cast<char*>(l4_utcb_mr_u(_utcb)->mr);
00643     }
00644
00652
00659 template< typename T >
00660 bool put(T *buf, unsigned long size)
00661 {
00662     size *= sizeof(T);
00663     _pos = cxx::Type_traits<T>::align(_pos);
00664     if (Utcb_stream_check::check_utcb_data_offset(_pos + size))
00665         return false;
00666
00667     __builtin_memcpy(_current_msg + _pos, buf, size);
00668     _pos += size;
00669     return true;
00670 }

```

```

00671
00672 template< typename T >
00673 bool put(T const &v)
00674 {
00675     _pos = cxx::Type_traits<T>::align(_pos);
00676     if (Utcstream_check::check_utcb_data_offset(_pos + sizeof(T)))
00677         return false;
00678
00679     *(reinterpret_cast<T*>(_current_msg + _pos)) = v;
00680     _pos += sizeof(T);
00681     return true;
00682 }
00683
00684 int put(Varg const &va)
00685 {
00686     put(va.tag());
00687     put(va.data(), va.length());
00688
00689     return 0;
00690 }
00691
00692 template< typename T >
00693 int put(Varg_t<T> const &va)
00694 { return put(static_cast<Varg const &>(va)); }
00695
00696 l4_msgtag_t tag() const { return _tag; }
00697
00698 l4_msgtag_t &tag() { return _tag; }
00699
00700 inline bool put_snd_item(Snd_fpage const &);
00701
00702 inline l4_msgtag_t send(l4_cap_idx_t dst, long proto = 0, unsigned flags = 0);
00703
00704 inline l4_utcb_t *utcb() const { return _utcb; }
00705 #if 0
00706 unsigned long tell() const
00707 {
00708     unsigned w = l4_bytes_to_mwords(_pos) - _current_item * 2;
00709     _tag = l4_msgtag(0, w, _current_item, 0);
00710 }
00711 #endif
00712 public:
00713     l4_msgtag_t prepare_ipc(long proto = 0, unsigned flags = 0)
00714     {
00715         unsigned w = l4_bytes_to_mwords(_pos) - _current_item * 2;
00716         return l4_msgtag(proto, w, _current_item, flags);
00717     }
00718
00719 // XXX: this is a hack for <l4/sys/cxx/ipc_server> adaption
00720 void set_ipc_params(l4_msgtag_t tag)
00721 {
00722     _pos = (tag.words() + tag.items() * 2) * sizeof(l4_umword_t);
00723     _current_item = tag.items();
00724 }
00725 protected:
00726     l4_msgtag_t _tag;
00727     l4_utcb_t * _utcb;
00728     char *_current_msg;
00729     unsigned _pos;
00730     unsigned char _current_item;
00731 };
00732
00733 class Iostream : public Istream, public Ostream
00734 {
00735 public:
00736     explicit Iostream(l4_utcb_t *utcb)
00737     : Istream(utcb), Ostream(utcb)
00738     {}
00739
00740 // disambiguate those functions
00741     l4_msgtag_t tag() const { return Istream::tag(); }
00742     l4_msgtag_t &tag() { return Istream::tag(); }
00743     l4_utcb_t *utcb() const { return Istream::utcb(); }
00744
00745     void reset()
00746     {
00747         Istream::reset();
00748         Ostream::reset();
00749     }
00750
00751
00752
00753

```

```

00829
00830 using Istream::get;
00831 using Istream::put;
00832 using Ostream::put;
00833
00835
00840
00856 inline l4_msgtag_t call(l4_cap_idx_t dst, l4_timeout_t timeout, long proto = 0);
00857 inline l4_msgtag_t call(l4_cap_idx_t dst, long proto = 0);
00858
00874 inline l4_msgtag_t reply_and_wait(l4_umword_t *src_dst, long proto = 0)
00875 { return reply_and_wait(src_dst, L4_IPC_SEND_TIMEOUT_0, proto); }
00876
00877 inline l4_msgtag_t send_and_wait(l4_cap_idx_t dest, l4_umword_t *src,
00878                                 long proto = 0)
00879 { return send_and_wait(dest, src, L4_IPC_SEND_TIMEOUT_0, proto); }
00880
00897 inline l4_msgtag_t reply_and_wait(l4_umword_t *src_dst,
00898                                 l4_timeout_t timeout, long proto = 0);
00899 inline l4_msgtag_t send_and_wait(l4_cap_idx_t dest, l4_umword_t *src,
00900                                 l4_timeout_t timeout, long proto = 0);
00901 inline l4_msgtag_t reply(l4_timeout_t timeout, long proto = 0);
00902 inline l4_msgtag_t reply(long proto = 0)
00903 { return reply(L4_IPC_SEND_TIMEOUT_0, proto); }
00904
00906 };
00907
00908
00909 inline bool
00910 Ostream::put_snd_item(Snd_fpage const &v)
00911 {
00912     typedef Snd_fpage T;
00913     _pos = cxx::Type_traits<Snd_fpage>::align(_pos);
00914     if (Utcb_stream_check::check_utcb_data_offset(_pos + sizeof(T))
00915         return false;
00916
00917     *(reinterpret_cast<T*>(_current_msg + _pos)) = v;
00918     _pos += sizeof(T);
00919     ++_current_item;
00920     return true;
00921 }
00922
00923
00924 inline bool
00925 Istream::put(Rcv_fpage const &item)
00926 {
00927     unsigned words = item.forward_mappings() ? 3 : 2;
00928     if (_current_buf >= L4_UTCB_GENERIC_BUFFERS_SIZE - words - 1)
00929         return false;
00930
00931     l4_utcb_br_u(_utcb)->bdr &= ~L4_BDR_OFFSET_MASK;
00932
00933     l4_umword_t *buf
00934         = reinterpret_cast<l4_umword_t *>(&l4_utcb_br_u(_utcb)->br[_current_buf]);
00935     *buf++ = item.base_x();
00936     *buf++ = item.data();
00937     if (item.forward_mappings())
00938         *buf++ = item.rcv_task();
00939     _current_buf += words;
00940     return true;
00941 }
00942
00943
00944 inline bool
00945 Istream::put(Small_buf const &item)
00946 {
00947     if (_current_buf >= L4_UTCB_GENERIC_BUFFERS_SIZE - 2)
00948         return false;
00949
00950     l4_utcb_br_u(_utcb)->bdr &= ~L4_BDR_OFFSET_MASK;
00951
00952     reinterpret_cast<Small_buf*>(&l4_utcb_br_u(_utcb)->br[_current_buf]) = item;
00953     _current_buf += 1;
00954     return true;
00955 }
00956
00957
00958 inline l4_msgtag_t
00959 Ostream::send(l4_cap_idx_t dst, long proto, unsigned flags)
00960 {
00961     l4_msgtag_t tag = prepare_ipc(proto, L4_MSGTAG_FLAGS & flags);
00962     return l4_ipc_send(dst, _utcb, tag, L4_IPC_NEVER);
00963 }
00964
00965 inline l4_msgtag_t
00966 Iostream::call(l4_cap_idx_t dst, l4_timeout_t timeout, long label)
00967 {

```

```

00968     l4_msgtag_t tag = prepare_ipc(label);
00969     tag = l4_ipc_call(dst, Ostream::_utcb, tag, timeout);
00970     Istream::tag() = tag;
00971     Istream::_pos = 0;
00972     return tag;
00973 }
00974
00975 inline l4_msgtag_t
00976 Iostream::call(l4_cap_idx_t dst, long label)
00977 { return call(dst, L4_IPC_NEVER, label); }
00978
00979
00980 inline l4_msgtag_t
00981 Iostream::reply_and_wait(l4_umword_t *src_dst, l4_timeout_t timeout, long proto)
00982 {
00983     l4_msgtag_t tag = prepare_ipc(proto);
00984     tag = l4_ipc_reply_and_wait(Ostream::_utcb, tag, src_dst, timeout);
00985     Istream::tag() = tag;
00986     Istream::_pos = 0;
00987     return tag;
00988 }
00989
00990
00991 inline l4_msgtag_t
00992 Iostream::send_and_wait(l4_cap_idx_t dest, l4_umword_t *src,
00993                        l4_timeout_t timeout, long proto)
00994 {
00995     l4_msgtag_t tag = prepare_ipc(proto);
00996     tag = l4_ipc_send_and_wait(dest, Ostream::_utcb, tag, src, timeout);
00997     Istream::tag() = tag;
00998     Istream::_pos = 0;
00999     return tag;
01000 }
01001
01002 inline l4_msgtag_t
01003 Iostream::reply(l4_timeout_t timeout, long proto)
01004 {
01005     l4_msgtag_t tag = prepare_ipc(proto);
01006     tag = l4_ipc_send(L4_INVALID_CAP | L4_SYSF_REPLY, Ostream::_utcb, tag, timeout);
01007     Istream::tag() = tag;
01008     Istream::_pos = 0;
01009     return tag;
01010 }
01011
01012 inline l4_msgtag_t
01013 Istream::wait(l4_umword_t *src, l4_timeout_t timeout)
01014 {
01015     l4_msgtag_t res;
01016     res = l4_ipc_wait(_utcb, src, timeout);
01017     tag() = res;
01018     _pos = 0;
01019     return res;
01020 }
01021
01022
01023 inline l4_msgtag_t
01024 Istream::receive(l4_cap_idx_t src, l4_timeout_t timeout)
01025 {
01026     l4_msgtag_t res;
01027     res = l4_ipc_receive(src, _utcb, timeout);
01028     tag() = res;
01029     _pos = 0;
01030     return res;
01031 }
01032
01033 } // namespace Ipc
01034 } // namespace L4
01035
01044 inline L4::Ipc::Istream &operator » (L4::Ipc::Istream &s, bool &v) { s.get(v); return s; }
01045 inline L4::Ipc::Istream &operator » (L4::Ipc::Istream &s, int &v) { s.get(v); return s; }
01046 inline L4::Ipc::Istream &operator » (L4::Ipc::Istream &s, long int &v) { s.get(v); return s; }
01047 inline L4::Ipc::Istream &operator » (L4::Ipc::Istream &s, long long int &v) { s.get(v); return s; }
01048 inline L4::Ipc::Istream &operator » (L4::Ipc::Istream &s, unsigned int &v) { s.get(v); return s; }
01049 inline L4::Ipc::Istream &operator » (L4::Ipc::Istream &s, unsigned long int &v) { s.get(v); return s; }
01050 inline L4::Ipc::Istream &operator » (L4::Ipc::Istream &s, unsigned long long int &v) { s.get(v);
    return s; }
01051 inline L4::Ipc::Istream &operator » (L4::Ipc::Istream &s, short int &v) { s.get(v); return s; }
01052 inline L4::Ipc::Istream &operator » (L4::Ipc::Istream &s, unsigned short int &v) { s.get(v); return s; }
01053 inline L4::Ipc::Istream &operator » (L4::Ipc::Istream &s, char &v) { s.get(v); return s; }
01054 inline L4::Ipc::Istream &operator » (L4::Ipc::Istream &s, unsigned char &v) { s.get(v); return s; }
01055 inline L4::Ipc::Istream &operator » (L4::Ipc::Istream &s, signed char &v) { s.get(v); return s; }
01056 inline L4::Ipc::Istream &operator « (L4::Ipc::Istream &s, L4::Ipc::Rcv_fpage const &v) { s.put(v);
    return s; }
01057 inline L4::Ipc::Istream &operator « (L4::Ipc::Istream &s, L4::Ipc::Small_buf const &v) { s.put(v);
    return s; }

```

```

01058 inline L4::Ipc::Istream &operator » (L4::Ipc::Istream &s, L4::Ipc::Snd_fpage &v)
01059 {
01060     l4_umword_t b, d;
01061     s » b » d;
01062     v = L4::Ipc::Snd_fpage(b, d);
01063     return s;
01064 }
01065 inline L4::Ipc::Istream &operator » (L4::Ipc::Istream &s, L4::Ipc::Varg &v)
01066 { s.get(&v); return s; }
01067
01068
01077 inline
01078 L4::Ipc::Istream &operator » (L4::Ipc::Istream &s, l4_msgtag_t &v)
01079 {
01080     v = s.tag();
01081     return s;
01082 }
01083
01101 template< typename T >
01102 inline
01103 L4::Ipc::Istream &operator » (L4::Ipc::Istream &s,
01104                               L4::Ipc::Internal::Buf_in<T> const &v)
01105 {
01106     unsigned long si;
01107     if (s.get(si) && s.has_more<T>(si))
01108         v.set_size(s.get(L4::Ipc::Msg_ptr<T>(v.buf()), si));
01109     else
01110         v.set_size(0);
01111     return s;
01112 }
01113
01128 template< typename T >
01129 inline
01130 L4::Ipc::Istream &operator » (L4::Ipc::Istream &s,
01131                               L4::Ipc::Msg_ptr<T> const &v)
01132 {
01133     s.get(v);
01134     return s;
01135 }
01136
01149 template< typename T >
01150 inline
01151 L4::Ipc::Istream &operator » (L4::Ipc::Istream &s,
01152                               L4::Ipc::Internal::Buf_cp_in<T> const &v)
01153 {
01154     unsigned long sz;
01155     s.get(sz);
01156     v.size() = s.get(v.buf(), cxx::min(v.size(), sz));
01157     return s;
01158 }
01159
01170 template< typename T >
01171 inline
01172 L4::Ipc::Istream &operator » (L4::Ipc::Istream &s,
01173                               L4::Ipc::Str_cp_in<T> const &v)
01174 {
01175     unsigned long sz;
01176     s.get(sz);
01177     unsigned long rsz = s.get(v.buf(), cxx::min(v.size(), sz));
01178     if (rsz < v.size() && v.buf()[rsz - 1])
01179         ++rsz; // add the zero termination behind the received data
01180
01181     if (rsz != 0)
01182         v.buf()[rsz - 1] = 0;
01183
01184     v.size() = rsz;
01185     return s;
01186 }
01187
01188
01197 inline L4::Ipc::Ostream &operator « (L4::Ipc::Ostream &s, bool v) { s.put(v); return s; }
01198 inline L4::Ipc::Ostream &operator « (L4::Ipc::Ostream &s, int v) { s.put(v); return s; }
01199 inline L4::Ipc::Ostream &operator « (L4::Ipc::Ostream &s, long int v) { s.put(v); return s; }
01200 inline L4::Ipc::Ostream &operator « (L4::Ipc::Ostream &s, long long int v) { s.put(v); return s; }
01201 inline L4::Ipc::Ostream &operator « (L4::Ipc::Ostream &s, unsigned int v) { s.put(v); return s; }
01202 inline L4::Ipc::Ostream &operator « (L4::Ipc::Ostream &s, unsigned long int v) { s.put(v); return s; }
01203 inline L4::Ipc::Ostream &operator « (L4::Ipc::Ostream &s, unsigned long long int v) { s.put(v); return
s; }
01204 inline L4::Ipc::Ostream &operator « (L4::Ipc::Ostream &s, short int v) { s.put(v); return s; }
01205 inline L4::Ipc::Ostream &operator « (L4::Ipc::Ostream &s, unsigned short int v) { s.put(v); return s;
}
01206 inline L4::Ipc::Ostream &operator « (L4::Ipc::Ostream &s, char v) { s.put(v); return s; }
01207 inline L4::Ipc::Ostream &operator « (L4::Ipc::Ostream &s, unsigned char v) { s.put(v); return s; }
01208 inline L4::Ipc::Ostream &operator « (L4::Ipc::Ostream &s, signed char v) { s.put(v); return s; }
01209 inline L4::Ipc::Ostream &operator « (L4::Ipc::Ostream &s, L4::Ipc::Snd_fpage const &v) {
s.put_snd_item(v); return s; }
01210 template< typename T >

```

```

01211 inline L4::Ipc::Ostream &operator « (L4::Ipc::Ostream &s, L4::Cap<T> const &v)
01212 { s « L4::Ipc::Snd_fpage(v.fpage()); return s; }
01213
01214 inline L4::Ipc::Ostream &operator « (L4::Ipc::Ostream &s, L4::Ipc::Varg const &v)
01215 { s.put(v); return s; }
01216 template< typename T >
01217 inline L4::Ipc::Ostream &operator « (L4::Ipc::Ostream &s, L4::Ipc::Varg_t<T> const &v)
01218 { s.put(v); return s; }
01219
01231 inline
01232 L4::Ipc::Ostream &operator « (L4::Ipc::Ostream &s, l4_msgtag_t const &v)
01233 {
01234     s.tag() = v;
01235     return s;
01236 }
01237
01246 template< typename T >
01247 inline
01248 L4::Ipc::Ostream &operator « (L4::Ipc::Ostream &s,
01249                               L4::Ipc::Internal::Buf_cp_out<T> const &v)
01250 {
01251     s.put(v.size());
01252     s.put(v.buf(), v.size());
01253     return s;
01254 }
01255
01268 inline
01269 L4::Ipc::Ostream &operator « (L4::Ipc::Ostream &s, char const *v)
01270 {
01271     unsigned long l = __builtin_strlen(v) + 1;
01272     s.put(l);
01273     s.put(v, l);
01274     return s;
01275 }
01276
01277 namespace L4 { namespace Ipc {
01287 template< typename T >
01288 inline
01289 T read(Istream &s) { T t; s » t; return t; }
01290
01291 } // namespace Ipc
01292 } // namespace L4

```

## 16.199 ipc\_timeout\_queue

```

00001 // vim:set ft=cpp: -*- Mode: C++ -*-
00002 /*
00003  * (c) 2014 Steffen Liebergeld <steffen.liebergeld@kernkonzept.com>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007 #pragma once
00008
00009 #include <l4/cxx/hlist>
00010 #include <l4/sys/cxx/ipc_server_loop>
00011
00012 namespace L4 { namespace Ipc_svr {
00013
00018 class Timeout : public cxx::H_list_item
00019 {
00020     friend class Timeout_queue;
00021 public:
00023     Timeout() : _timeout(0) {}
00024
00026     virtual ~Timeout() = 0;
00027
00034     virtual void expired() = 0;
00035
00042     l4_kernel_clock_t timeout() const
00043     { return _timeout; }
00044
00045 private:
00046     l4_kernel_clock_t _timeout;
00047 };
00048
00049 inline Timeout::~~Timeout() {}
00050
00055 class Timeout_queue
00056 {
00057 public:
00059     typedef L4::Ipc_svr::Timeout Timeout;
00060
00065     l4_kernel_clock_t next_timeout() const

```



```

00066 {
00067     if (auto e = _timeouts.front())
00068         return e->timeout();
00069     return 0;
00071 }
00072
00081 bool timeout_expired(l4_kernel_clock_t now) const
00082 {
00083     l4_kernel_clock_t next = next_timeout();
00084     return (next != 0) && (next <= now);
00085 }
00086
00091 void handle_expired_timeouts(l4_kernel_clock_t now)
00092 {
00093     while (!_timeouts.empty())
00094     {
00095         Queue::Iterator top = _timeouts.begin();
00096         if ((*top)->_timeout > now)
00097             return;
00098
00099         Timeout *t = *top;
00100         top = _timeouts.erase(top);
00101         t->expired();
00102     }
00103 }
00104
00111 void add(Timeout *timeout, l4_kernel_clock_t time)
00112 {
00113     timeout->_timeout = time;
00114     Queue::Iterator i = _timeouts.begin();
00115     while (i != _timeouts.end() && (*i)->timeout() < time)
00116         ++i;
00117     _timeouts.insert_before(timeout, i);
00119 }
00120
00126 void remove(Timeout *timeout)
00127 {
00128     _timeouts.remove(timeout);
00129 }
00130
00131 private:
00132     typedef cxx::H_list<Timeout> Queue;
00133     Queue _timeouts;
00134 };
00135
00149 template< typename HOOKS, typename BR_MAN = Br_manager_no_buffers >
00150 class Timeout_queue_hooks : public BR_MAN
00151 {
00152     l4_kernel_clock_t _now()
00153     { return static_cast<HOOKS*>(this)->now(); }
00154
00155     unsigned _timeout_br()
00156     { return this->first_free_br(); }
00157
00158 public:
00160     l4_timeout_t timeout()
00161     {
00162         l4_kernel_clock_t t = queue.next_timeout();
00163         if (t)
00164             return l4_timeout(L4_IPC_TIMEOUT_0, l4_timeout_abs(t, _timeout_br()));
00165         return L4_IPC_SEND_TIMEOUT_0;
00166     }
00167
00169     void setup_wait(l4_utcb_t *utcb, L4::Ipc_svr::Reply_mode mode)
00170     {
00171         // we must handle the timer only when called after a possible reply
00172         // otherwise we probably destroy the reply message.
00173         if (mode == L4::Ipc_svr::Reply_separate)
00174         {
00175             l4_kernel_clock_t now = _now();
00176             if (queue.timeout_expired(now))
00177                 queue.handle_expired_timeouts(now);
00178         }
00179
00180         BR_MAN::setup_wait(utcb, mode);
00181     }
00182
00184     L4::Ipc_svr::Reply_mode before_reply(l4_msgtag_t, l4_utcb_t *)
00185     {
00186         // split up reply and wait when a timeout has expired
00187         if (queue.timeout_expired(_now()))
00188             return L4::Ipc_svr::Reply_separate;
00189         return L4::Ipc_svr::Reply_compound;
00190     }
00191 }

```



## 16.201 l4iostream

[Go to the documentation of this file.](#)

```

00001 // -*- Mode: C++ -*-
00002 // vim:ft=cpp
00007 /*
00008  * (c) 2004-2009 Alexander Warg <warg@os.inf.tu-dresden.de>
00009  *      economic rights: Technische Universität Dresden (Germany)
00010  *
00011  * License: see LICENSE.spdx (in this directory or the directories above)
00012  */
00013 #pragma once
00014
00015 #include <l4/cxx/basic_ostream>
00016 #include <l4/sys/types.h>
00017 #include <l4/sys/capability>
00018
00019 inline
00020 L4::BasicOStream &operator << (L4::BasicOStream &o, l4_msgtag_t const &tag)
00021 {
00022     L4::IOBackend::Mode m = o.be_mode();
00023     o << "[l=" << L4::dec << tag.label() << "; w=" << tag.words() << "; i="
00024         << tag.items() << "];";
00025     o.be_mode(m);
00026     return o;
00027 }
00028
00029 template<typename T>
00030 inline
00031 L4::BasicOStream &operator << (L4::BasicOStream &o, L4::Cap<T> const &cap)
00032 {
00033     o << "[C:" << L4::n_hex(cap.cap()) << "];";
00034     return o;
00035 }

```

## 16.202 l4/cxx/l4types.h File Reference


L4 Types.

```


#include <l4/sys/types.h>
#include <l4/cxx/basic_ostream>

```

Include dependency graph for l4types.h:



This graph shows which files directly or indirectly include this file:



## 16.202.1 Detailed Description

[L4](#) Types.

Definition in file [l4types.h](#).

## 16.203 l4types.h

[Go to the documentation of this file.](#)

```

00001
00005 /*
00006  * (c) 2004-2009 Alexander Warg <warg@os.inf.tu-dresden.de>
00007  *     economic rights: Technische Universität Dresden (Germany)
00008  *
00009  * License: see LICENSE.spdx (in this directory or the directories above)
00010  */
00011 #pragma once
00012
00013 #include <l4/sys/types.h>
00014 #include <l4/cxx/basic_ostream>

```

## 16.204 list

```

00001 // vi:set ft=c++: -*- Mode: C++ -*-
00002 /*
00003  * (c) 2008-2009 Alexander Warg <warg@os.inf.tu-dresden.de>
00004  *     economic rights: Technische Universität Dresden (Germany)
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00008
00009 #pragma once
00010
00011 #include <l4/cxx/type_traits>
00012 #include <l4/cxx/std_alloc>
00013 #include <l4/cxx/std_ops>
00014
00015 namespace cxx {
00016 /*
00017  * Classes: List_item, List<D, Alloc>
00018  */
00019
00020 class List_item
00021 {
00022 public:
00023     class Iter

```

```

00035 {
00036 public:
00037     Iter(List_item *c, List_item *f) noexcept : _c(c), _f(f) {}
00038     Iter(List_item *f = 0) noexcept : _c(f), _f(f) {}
00039
00040     List_item *operator * () const noexcept { return _c; }
00041     List_item *operator -> () const noexcept { return _c; }
00042     Iter &operator ++ () noexcept
00043     {
00044         if (!_f)
00045             _c = 0;
00046         else
00047             _c = _c->get_next_item();
00048
00049         if (_c == _f)
00050             _c = 0;
00051
00052         return *this;
00053     }
00054
00055     Iter operator ++ (int) noexcept
00056     { Iter o = *this; operator ++ (); return o; }
00057
00058     Iter &operator -- () noexcept
00059     {
00060         if (!_f)
00061             _c = 0;
00062         else
00063             _c = _c->get_prev_item();
00064
00065         if (_c == _f)
00066             _c = 0;
00067
00068         return *this;
00069     }
00070
00071     Iter operator -- (int) noexcept
00072     { Iter o = *this; operator -- (); return o; }
00073
00075     List_item *remove_me() noexcept
00076     {
00077         if (!_c)
00078             return 0;
00079
00080         List_item *l = _c;
00081         operator ++ ();
00082         l->remove_me();
00083
00084         if (_f == l)
00085             _f = _c;
00086
00087         return l;
00088     }
00089
00090 private:
00091     List_item *_c, *_f;
00092 };
00093
00107 template< typename T, bool Poly = false>
00108 class T_iter : public Iter
00109 {
00110 private:
00111     static bool const P = !Conversion<const T*, const List_item *>::exists
00112         || Poly;
00113
00114     static List_item *cast_to_li(T *i, Int_to_type<true>) noexcept
00115     { return dynamic_cast<List_item*>(i); }
00116
00117     static List_item *cast_to_li(T *i, Int_to_type<false>) noexcept
00118     { return i; }
00119
00120     static T *cast_to_type(List_item *i, Int_to_type<true>) noexcept
00121     { return dynamic_cast<T*>(i); }
00122
00123     static T *cast_to_type(List_item *i, Int_to_type<false>) noexcept
00124     { return static_cast<T*>(i); }
00125
00126 public:
00127
00128     template< typename O >
00129     explicit T_iter(T_iter<O> const &o) noexcept
00130     : Iter(o) { dynamic_cast<T*>(&o); }
00131
00132     //TIter(CListItem *f) : Iter(f) {}
00133     T_iter(T *f = 0) noexcept : Iter(cast_to_li(f, Int_to_type<P>())) {}
00134     T_iter(T *c, T *f) noexcept
00135     : Iter(cast_to_li(c, Int_to_type<P>()),

```

```

00136 cast_to_li(f, Int_to_type<P>())
00137 {}
00138
00139 inline T *operator * () const noexcept
00140 { return cast_to_type(Iter::operator * (), Int_to_type<P>()); }
00141 inline T *operator -> () const noexcept
00142 { return operator * (); }
00143
00144 T_iter<T, Poly> operator ++ (int) noexcept
00145 { T_iter<T, Poly> o = *this; Iter::operator ++ (); return o; }
00146 T_iter<T, Poly> operator -- (int) noexcept
00147 { T_iter<T, Poly> o = *this; Iter::operator -- (); return o; }
00148 T_iter<T, Poly> &operator ++ () noexcept
00149 { Iter::operator ++ (); return *this; }
00150 T_iter<T, Poly> &operator -- () noexcept
00151 { Iter::operator -- (); return *this; }
00152 inline T *remove_me() noexcept;
00153 };
00154
00155 List_item() noexcept : _n(this), _p(this) {}
00156
00157 protected:
00158 List_item(List_item const &) noexcept : _n(this), _p(this) {}
00159
00160 public:
00162 List_item *get_prev_item() const noexcept { return _p; }
00163
00165 List_item *get_next_item() const noexcept { return _n; }
00166
00168 void insert_prev_item(List_item *p) noexcept
00169 {
00170     p->_p->_n = this;
00171     List_item *pr = p->_p;
00172     p->_p = _p;
00173     _p->_n = p;
00174     _p = pr;
00175 }
00176
00178 void insert_next_item(List_item *p) noexcept
00179 {
00180     p->_p->_n = _n;
00181     p->_p = this;
00182     _n->_p = p;
00183     _n = p;
00184 }
00185
00187 void remove_me() noexcept
00188 {
00189     if (_p != this)
00190     {
00191         _p->_n = _n;
00192         _n->_p = _p;
00193     }
00194     _p = _n = this;
00195 }
00196
00205 template< typename C, typename N >
00206 static inline C *push_back(C *head, N *p) noexcept;
00207
00216 template< typename C, typename N >
00217 static inline C *push_front(C *head, N *p) noexcept;
00218
00227 template< typename C, typename N >
00228 static inline C *remove(C *head, N *p) noexcept;
00229
00230 private:
00231 List_item *_n, *_p;
00232 };
00233
00234
00235 /* IMPLEMENTATION -----*/
00236 template< typename C, typename N >
00237 C *List_item::push_back(C *h, N *p) noexcept
00238 {
00239     if (!p)
00240         return h;
00241     if (!h)
00242         return p;
00243     h->insert_prev_item(p);
00244     return h;
00245 }
00246
00247 template< typename C, typename N >
00248 C *List_item::push_front(C *h, N *p) noexcept
00249 {
00250     if (!p)
00251         return h;

```

```

00252     if (h)
00253         h->insert_prev_item(p);
00254     return p;
00255 }
00256
00257 template< typename C, typename N >
00258 C *List_item::remove(C *h, N *p) noexcept
00259 {
00260     if (!p)
00261         return h;
00262     if (!h)
00263         return 0;
00264     if (h == p)
00265     {
00266         if (p == p->_n)
00267             h = 0;
00268         else
00269             h = static_cast<C*>(p->_n);
00270     }
00271     p->remove_me();
00272
00273     return h;
00274 }
00275
00276 template< typename T, bool Poly >
00277 inline
00278 T *List_item::T_iter<T, Poly>::remove_me() noexcept
00279 { return cast_to_type(Iter::remove_me(), Int_to_type<P>()); }
00280
00281
00282 template< typename T >
00283 class T_list_item : public List_item
00284 {
00285 public:
00286     T *next() const { return static_cast<T*>(List_item::get_next_item()); }
00287     T *prev() const { return static_cast<T*>(List_item::get_prev_item()); }
00288 };
00289
00290
00291 template< typename LI >
00292 class L_list
00293 {
00294 private:
00295     LI *_h;
00296
00297 public:
00298     L_list() : _h(0) {}
00299
00300     void push_front(LI *e) { _h = LI::push_front(_h, e); }
00301     void push_back(LI *e) { _h = LI::push_back(_h, e); }
00302     void insert_before(LI *e, LI *p)
00303     {
00304         p->insert_prev_item(e);
00305         if (_h == p)
00306             _h = e;
00307     }
00308     void insert_after(LI *e, LI *p) { p->insert_next_item(e); }
00309
00310     void remove(LI *e)
00311     { _h = LI::remove(_h, e); }
00312
00313     LI *head() const { return _h; }
00314 };
00315
00316
00322 template< typename D, template<typename A> class Alloc = New_allocator >
00323 class List
00324 {
00325 private:
00326     class E : public List_item
00327     {
00328     public:
00329         E(D const &d) noexcept : data(d) {}
00330         D data;
00331     };
00332
00333 public:
00334     class Node : private E
00335     {};
00336
00337     typedef Alloc<Node> Node_alloc;
00338
00343     class Iter
00344     {
00345     private:
00346         List_item::T_iter<E> _i;
00347

```

```

00348 public:
00349     Iter(E *e) noexcept : _i(e) {}
00350
00351     D &operator * () const noexcept { return (*_i)->data; }
00352     D &operator -> () const noexcept { return (*_i)->data; }
00353
00354     Iter operator ++ (int) noexcept
00355     { Iter o = *this; operator ++ (); return o; }
00356     Iter operator -- (int) noexcept
00357     { Iter o = *this; operator -- (); return o; }
00358     Iter &operator ++ () noexcept { ++_i; return *this; }
00359     Iter &operator -- () noexcept { --_i; return *this; }
00360
00362     operator E* () const noexcept { return *_i; }
00363 };
00364
00365 List(Alloc<Node> const &a = Alloc<Node>()) noexcept : _h(0), _l(0), _a(a) {}
00366
00368 void push_back(D const &d) noexcept
00369 {
00370     void *n = _a.alloc();
00371     if (!n) return;
00372     _h = E::push_back(_h, new (n) E(d));
00373     ++_l;
00374 }
00375
00377 void push_front(D const &d) noexcept
00378 {
00379     void *n = _a.alloc();
00380     if (!n) return;
00381     _h = E::push_front(_h, new (n) E(d));
00382     ++_l;
00383 }
00384
00386 void remove(Iter const &i) noexcept
00387 { E *e = i; _h = E::remove(_h, e); --_l; _a.free(e); }
00388
00390 unsigned long size() const noexcept { return _l; }
00391
00393 D const &operator [] (unsigned long idx) const noexcept
00394 { Iter i = _h; for (; idx && *i; ++i, --idx) { } return *i; }
00395
00397 D &operator [] (unsigned long idx) noexcept
00398 { Iter i = _h; for (; idx && *i; ++i, --idx) { } return *i; }
00399
00401 Iter items() noexcept { return Iter(_h); }
00402
00403 private:
00404     E *_h;
00405     unsigned _l;
00406     Alloc<Node> _a;
00407 };
00408
00409
00410 };
00411

```

## 16.205 list\_alloc

```

00001 // vim:set ft=cpp: -*- Mode: C++ -*-
00002 /*
00003  * (c) 2008-2009 Alexander Warg <warg@os.inf.tu-dresden.de>,
00004  *      Torsten Frenzel <frenzel@os.inf.tu-dresden.de>
00005  *      economic rights: Technische Universität Dresden (Germany)
00006  *
00007  * License: see LICENSE.spdx (in this directory or the directories above)
00008  */
00009
00010 #pragma once
00011
00012 #include <l4/cxx/arith>
00013 #include <l4/cxx/minmax>
00014 #include <l4/cxx/type_traits>
00015 #include <l4/sys/consts.h>
00016
00017 namespace cxx {
00018
00022 class List_alloc
00023 {
00024 private:
00025     friend class List_alloc_sanity_guard;
00026
00027     struct Mem_block

```



```

00028 {
00029     Mem_block *next;
00030     unsigned long size;
00031 };
00032
00033 Mem_block *_first;
00034
00035 inline void check_overlap(void *, unsigned long );
00036 inline void sanity_check_list(char const *, char const *);
00037 inline void merge();
00038
00039 public:
00040
00047 List_alloc() : _first(0) {}
00048
00061 inline void free(void *block, unsigned long size, bool initial_free = false);
00062
00077 inline void *alloc(unsigned long size, unsigned long align,
00078                   unsigned long lower = 0, unsigned long upper = ~0UL);
00079
00100 inline void *alloc_max(unsigned long min, unsigned long *max,
00101                       unsigned long align, unsigned granularity,
00102                       unsigned long lower = 0, unsigned long upper = ~0UL);
00103
00109 inline unsigned long avail();
00110
00111 template <typename DBG>
00112 void dump_free_list(DBG &out);
00113 };
00114
00115 #if !defined (CXX_LIST_ALLOC_SANITY)
00116 class List_alloc_sanity_guard
00117 {
00118 public:
00119     List_alloc_sanity_guard(List_alloc *, char const *)
00120     {}
00121
00122 };
00123
00124
00125 void
00126 List_alloc::check_overlap(void *, unsigned long )
00127 {}
00128
00129 void
00130 List_alloc::sanity_check_list(char const *, char const *)
00131 {}
00132
00133 #else
00134
00135 class List_alloc_sanity_guard
00136 {
00137 private:
00138     List_alloc *a;
00139     char const *func;
00140
00141 public:
00142     List_alloc_sanity_guard(List_alloc *a, char const *func)
00143     : a(a), func(func)
00144     { a->sanity_check_list(func, "entry"); }
00145
00146     ~List_alloc_sanity_guard()
00147     { a->sanity_check_list(func, "exit"); }
00148 };
00149
00150 void
00151 List_alloc::check_overlap(void *b, unsigned long s)
00152 {
00153     unsigned long const mb_align = (1UL << arith::Ld<sizeof(Mem_block)>::value) - 1;
00154     if ((unsigned long)b & mb_align)
00155     {
00156         L4::cerr << "List_alloc(FATAL): trying to free unaligned memory: "
00157                 << b << " align=" << arith::Ld<sizeof(Mem_block)>::value << "\n";
00158     }
00159
00160     Mem_block *c = _first;
00161     for (;c ; c = c->next)
00162     {
00163         unsigned long x_s = (unsigned long)b;
00164         unsigned long x_e = x_s + s;
00165         unsigned long b_s = (unsigned long)c;
00166         unsigned long b_e = b_s + c->size;
00167
00168         if ((x_s >= b_s && x_s < b_e)
00169             || (x_e > b_s && x_e <= b_e)
00170             || (b_s >= x_s && b_s < x_e)
00171             || (b_e > x_s && b_e <= x_e))

```

```

00172     {
00173         L4::cerr << "List_alloc(FATAL): trying to free memory that "
00174                 "is already free: \n ["
00175                 << (void*)x_s << '-' << (void*)x_e << ") overlaps ["
00176                 << (void*)b_s << '-' << (void*)b_e << ")\n";
00177     }
00178 }
00179 }
00180
00181 void
00182 List_alloc::sanity_check_list(char const *func, char const *info)
00183 {
00184     Mem_block *c = _first;
00185     for (; c ; c = c->next)
00186     {
00187         if (c->next)
00188         {
00189             if (c >= c->next)
00190             {
00191                 L4::cerr << "List_alloc(FATAL): " << func << ' (' << info
00192                         << "): list order violation\n";
00193             }
00194
00195             if (((unsigned long)c) + c->size > (unsigned long)c->next)
00196             {
00197                 L4::cerr << "List_alloc(FATAL): " << func << ' (' << info
00198                         << "): list order violation\n";
00199             }
00200         }
00201     }
00202 }
00203
00204 #endif
00205
00206 void
00207 List_alloc::merge()
00208 {
00209     List_alloc_sanity_guard __attribute__((unused)) guard(this, __func__);
00210     Mem_block *c = _first;
00211     while (c && c->next)
00212     {
00213         unsigned long f_start = reinterpret_cast<unsigned long>(c);
00214         unsigned long f_end   = f_start + c->size;
00215         unsigned long n_start = reinterpret_cast<unsigned long>(c->next);
00216
00217         if (f_end == n_start)
00218         {
00219             c->size += c->next->size;
00220             c->next = c->next->next;
00221             continue;
00222         }
00223
00224         c = c->next;
00225     }
00226 }
00227
00228 void
00229 List_alloc::free(void *block, unsigned long size, bool initial_free)
00230 {
00231     List_alloc_sanity_guard __attribute__((unused)) guard(this, __func__);
00232
00233     unsigned long const mb_align = (1UL << arith::Ld<sizeof(Mem_block)>::value) - 1;
00234
00235     if (initial_free)
00236     {
00237         // enforce alignment constraint on initial memory
00238         unsigned long nblock = (reinterpret_cast<unsigned long>(block) + mb_align)
00239                               & ~mb_align;
00240         size = (size - (nblock - reinterpret_cast<unsigned long>(block)))
00241              & ~mb_align;
00242         block = reinterpret_cast<void*>(nblock);
00243     }
00244     else
00245         // blow up size to the minimum aligned size
00246         size = (size + mb_align) & ~mb_align;
00247
00248     check_overlap(block, size);
00249
00250     Mem_block **c = &_first;
00251     Mem_block *next = 0;
00252
00253     if (*c)
00254     {
00255         while (*c && *c < block)
00256             c = &(*c)->next;
00257
00258         next = *c;

```

```

00259     }
00260
00261     *c = reinterpret_cast<Mem_block*>(block);
00262
00263     (*c)->next = next;
00264     (*c)->size = size;
00265
00266     merge();
00267 }
00268
00269 void *
00270 List_alloc::alloc_max(unsigned long min, unsigned long *max, unsigned long align,
00271                      unsigned granularity, unsigned long lower,
00272                      unsigned long upper)
00273 {
00274     List_alloc_sanity_guard __attribute__((unused)) guard(this, __func__);
00275
00276     unsigned char const mb_bits = arith::Ld<sizeof(Mem_block)>::value;
00277     unsigned long const mb_align = (1UL << mb_bits) - 1;
00278
00279     // blow minimum up to at least the minimum aligned size of a Mem_block
00280     min = l4_round_size(min, mb_bits);
00281     // truncate maximum to at least the size of a Mem_block
00282     *max = l4_trunc_size(*max, mb_bits);
00283     // truncate maximum size according to granularity
00284     *max = *max & ~(granularity - 1UL);
00285
00286     if (min > *max)
00287         return 0;
00288
00289     unsigned long almask = align ? (align - 1UL) : 0;
00290
00291     // minimum alignment is given by the size of a Mem_block
00292     if (almask < mb_align)
00293         almask = mb_align;
00294
00295     Mem_block **c = &_first;
00296     Mem_block **fit = 0;
00297     unsigned long max_fit = 0;
00298     unsigned long a_lower = (lower + almask) & ~almask;
00299
00300     for (; *c; c = &(*c)->next)
00301     {
00302         // address of free memory block
00303         unsigned long n_start = reinterpret_cast<unsigned long>(*c);
00304
00305         // block too small, next
00306         // XXX: maybe we can skip this and just do the test below
00307         if ((*c)->size < min)
00308             continue;
00309
00310         // block outside region, next
00311         if (upper < n_start || a_lower > n_start + (*c)->size)
00312             continue;
00313
00314         // aligned start address within the free block
00315         unsigned long a_start = (n_start + almask) & ~almask;
00316
00317         // check if aligned start address is behind the block, next
00318         if (a_start - n_start >= (*c)->size)
00319             continue;
00320
00321         a_start = a_start < a_lower ? a_lower : a_start;
00322
00323         // end address would overflow, next
00324         if (min > ~0UL - a_start)
00325             continue;
00326
00327         // block outside region, next
00328         if (a_start + min - 1UL > upper)
00329             continue;
00330
00331         // remaining size after subtracting the padding for the alignment
00332         unsigned long r_size = (*c)->size - a_start + n_start;
00333
00334         // upper limit can limit maximum size
00335         if (a_start + r_size - 1UL > upper)
00336             r_size = upper - a_start + 1UL;
00337
00338         // round down according to granularity
00339         r_size &= ~(granularity - 1UL);
00340
00341         // block too small
00342         if (r_size < min)
00343             continue;
00344
00345         if (r_size >= *max)

```

```

00346     {
00347         fit = c;
00348         max_fit = *max;
00349         break;
00350     }
00351
00352     if (r_size > max_fit)
00353     {
00354         max_fit = r_size;
00355         fit = c;
00356     }
00357 }
00358
00359 if (fit)
00360 {
00361     unsigned long n_start = reinterpret_cast<unsigned long>(*fit);
00362     unsigned long a_lower = (lower + almask) & ~almask;
00363     unsigned long a_start = (n_start + almask) & ~almask;
00364     a_start = a_start < a_lower ? a_lower : a_start;
00365     unsigned long r_size = (*fit)->size - a_start + n_start;
00366
00367     if (a_start > n_start)
00368     {
00369         (*fit)->size -= r_size;
00370         fit = &(*fit)->next;
00371     }
00372     else
00373         *fit = (*fit)->next;
00374
00375     *max = max_fit;
00376     if (r_size == max_fit)
00377         return reinterpret_cast<void *>(a_start);
00378
00379     Mem_block *m = reinterpret_cast<Mem_block*>(a_start + max_fit);
00380     m->next = *fit;
00381     m->size = r_size - max_fit;
00382     *fit = m;
00383     return reinterpret_cast<void *>(a_start);
00384 }
00385
00386 return 0;
00387 }
00388
00389 void *
00390 List_alloc::alloc(unsigned long size, unsigned long align, unsigned long lower,
00391                  unsigned long upper)
00392 {
00393     List_alloc_sanity_guard __attribute__((unused)) guard(this, __func__);
00394
00395     unsigned long const mb_align
00396         = (1UL << arith::Ld<sizeof(Mem_block)>::value) - 1;
00397
00398     // blow up size to the minimum aligned size
00399     size = (size + mb_align) & ~mb_align;
00400
00401     unsigned long almask = align ? (align - 1UL) : 0;
00402
00403     // minimum alignment is given by the size of a Mem_block
00404     if (almask < mb_align)
00405         almask = mb_align;
00406
00407     Mem_block **c = &_first;
00408     unsigned long a_lower = (lower + almask) & ~almask;
00409
00410     for (; *c; c=&(*c)->next)
00411     {
00412         // address of free memory block
00413         unsigned long n_start = reinterpret_cast<unsigned long>(*c);
00414
00415         // block too small, next
00416         // XXX: maybe we can skip this and just do the test below
00417         if ((*c)->size < size)
00418             continue;
00419
00420         // block outside region, next
00421         if (upper < n_start || a_lower > n_start + (*c)->size)
00422             continue;
00423
00424         // aligned start address within the free block
00425         unsigned long a_start = (n_start + almask) & ~almask;
00426
00427         // block too small after alignment, next
00428         if (a_start - n_start >= (*c)->size)
00429             continue;
00430
00431         a_start = a_start < a_lower ? a_lower : a_start;
00432

```

```

00433     // end address would overflow, next
00434     if (size > ~0UL - a_start)
00435         continue;
00436
00437     // block outside region, next
00438     if (a_start + size - 1UL > upper)
00439         continue;
00440
00441     // remaining size after subtracting the padding
00442     // for the alignment
00443     unsigned long r_size = (*c)->size - a_start + n_start;
00444
00445     // block too small
00446     if (r_size < size)
00447         continue;
00448
00449     if (a_start > n_start)
00450     {
00451         // have free space before the allocated block
00452         // shrink the block and set c to the next pointer of that
00453         // block
00454         (*c)->size -= r_size;
00455         c = &(*c)->next;
00456     }
00457     else
00458         // drop the block, c remains the next pointer of the
00459         // previous block
00460         *c = (*c)->next;
00461
00462     // allocated the whole remaining space
00463     if (r_size == size)
00464         return reinterpret_cast<void*>(a_start);
00465
00466     // add a new free block behind the allocated block
00467     Mem_block *m = reinterpret_cast<Mem_block*>(a_start + size);
00468     m->next = *c;
00469     m->size = r_size - size;
00470     *c = m;
00471     return reinterpret_cast<void *>(a_start);
00472 }
00473
00474 return 0;
00475 }
00476
00477 unsigned long
00478 List_alloc::avail()
00479 {
00480     List_alloc_sanity_guard __attribute__((unused)) guard(this, __FUNCTION__);
00481     Mem_block *c = _first;
00482     unsigned long a = 0;
00483     while (c)
00484     {
00485         a += c->size;
00486         c = c->next;
00487     }
00488     return a;
00489 }
00490
00491 template <typename DBG>
00492 void
00493 List_alloc::dump_free_list(DBG &out)
00494 {
00495     Mem_block *c = _first;
00496     while (c)
00497     {
00498         static constexpr char const *const unitstr[4] =
00499             { "Byte", "KiB", "MiB", "GiB" };
00500
00501         unsigned sz = c->size;
00502         unsigned i;
00503         for (i = 0; i < cxx::array_size(unitstr) && sz > 8 « 10; ++i)
00504             sz »= 10;
00505
00506         out.printf("%12p - %12p (%u %s)\n",
00507             c, reinterpret_cast<char *>(c) + c->size - 1, sz, unitstr[i]);
00508
00509         c = c->next;
00510     }
00511 }
00512 }
00513
00514 }

```


## 16.206 I4/cxx/lock\_guard.h File Reference

Lock guard implementation.

```
#include <pthread.h>
```

```
#include <stdlib.h>
```

Include dependency graph for lock\_guard.h:



### Data Structures

- class [L4::Lock\\_guard](#)

*Basic lock guard implementation that prevents forgotten unlocks on exit paths from a method or a block of code.*

### Namespaces

- namespace [L4](#)

*[L4](#) low-level kernel interface.*

## 16.206.1 Detailed Description

Lock guard implementation.

Definition in file [lock\\_guard.h](#).

## 16.207 lock\_guard.h

[Go to the documentation of this file.](#)

```
00001 // vim:set ft=cpp: -*- Mode: C++ -*-
00002 /*
00003  * Copyright (C) 2025 Kernkonzept GmbH.
00004  * Author(s): Martin Decky <martin.decky@kernkonzept.com>
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00008
00013
00014 #pragma once
00015
00016 #include <pthread.h>
```

```

00017 #include <stdlib.h>
00018
00019 namespace L4 {
00020
00044 class Lock_guard
00045 {
00046 public:
00047     Lock_guard() = delete;
00048     Lock_guard(const Lock_guard &) = delete;
00049     Lock_guard &operator=(const Lock_guard &) = delete;
00050
00059     explicit Lock_guard(pthread_mutex_t &lock) : _lock(&lock)
00060     {
00061         _status = pthread_mutex_lock(_lock);
00062     }
00063
00071     Lock_guard(Lock_guard &&guard) : _lock(guard._lock), _status(guard._status)
00072     {
00073         guard.release();
00074     }
00075
00090     Lock_guard &operator=(Lock_guard &&guard)
00091     {
00092         // Unlock the currently associated mutex (if any).
00093         reset();
00094
00095         // Move the state from the other guard.
00096         _lock = guard._lock;
00097         _status = guard._status;
00098
00099         // Release the mutex from the other guard.
00100         guard.release();
00101
00102         return *this;
00103     }
00104
00110     int status() const
00111     {
00112         return _status;
00113     }
00114
00126     ~Lock_guard()
00127     {
00128         reset();
00129     }
00130
00131 private:
00137     void release()
00138     {
00139         _lock = nullptr;
00140     }
00141
00150     void reset()
00151     {
00152         // No mutex might be associated with this lock guard only if the mutex has
00153         // been moved to a different lock guard.
00154         if (_lock)
00155         {
00156             _status = pthread_mutex_unlock(_lock);
00157             release();
00158         }
00159     }
00160
00161     pthread_mutex_t *_lock;
00162     int _status;
00163 };
00164
00165 } // namespace L4

```

## 16.208 I4/cxx/main\_thread File Reference

Main thread.





```

00019  * the GNU General Public License. This exception does not however
00020  * invalidate any other reasons why the executable file might be covered by
00021  * the GNU General Public License.
00022  */
00023
00024 #ifndef L4_CXX_MAIN_THREAD_H__
00025 #define L4_CXX_MAIN_THREAD_H__
00026
00027 #include <l4/cxx/thread>
00028
00029 namespace cxx {
00030     class MainThread : public Thread
00031     {
00032     public:
00033         MainThread() : Thread(true)
00034         {}
00035     };
00036 };
00037
00038 #endif /* L4_CXX_MAIN_THREAD_H__ */

```

## 16.210 minmax

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00002 /*
00003  * (c) 2008-2009 Alexander Warg <warg@os.inf.tu-dresden.de>
00004  *      economic rights: Technische Universität Dresden (Germany)
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00008 #pragma once
00009
00010 #include "type_traits"
00011
00012 namespace cxx
00013 {
00014     // trivial, used to terminate the variadic recursion
00015     template<typename A>
00016     constexpr A const &
00017     min(A const &a)
00018     { return a; }
00019
00020     template<typename A, typename ...ARGS>
00021     constexpr A const &
00022     min(A const &a1, A const &a2, ARGS const &...a)
00023     {
00024         return min((a1 <= a2) ? a1 : a2, a...);
00025     }
00026
00027     template<typename A, typename ...ARGS>
00028     constexpr A const &
00029     min(cxx::identity_t<A> const &a1,
00030         cxx::identity_t<A> const &a2,
00031         ARGS const &...a)
00032     {
00033         return min<A>((a1 <= a2) ? a1 : a2, a...);
00034     }
00035
00036     // trivial, used to terminate the variadic recursion
00037     template<typename A>
00038     constexpr A const &
00039     max(A const &a)
00040     { return a; }
00041
00042     template<typename A, typename ...ARGS>
00043     constexpr A const &
00044     max(A const &a1, A const &a2, ARGS const &...a)
00045     { return max((a1 >= a2) ? a1 : a2, a...); }
00046
00047     template<typename A, typename ...ARGS>
00048     constexpr A const &
00049     max(cxx::identity_t<A> const &a1,
00050         cxx::identity_t<A> const &a2,
00051         ARGS const &...a)
00052     {
00053         return max<A>((a1 >= a2) ? a1 : a2, a...);
00054     }
00055
00056     template<typename T1 >
00057     inline
00058     T1 clamp(T1 v, T1 lo, T1 hi)
00059     { return min(hi, max(lo, v)); }
00060 };

```

## 16.211 numeric

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00002 /*
00003  * Copyright (C) 2025 Kernkonzept GmbH.
00004  * Author(s): Martin Decky <martin.decky@kernkonzept.com>
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00008
00009 #pragma once
00010
00011 #include <l4/cxx/type_traits>
00012
00013 namespace cxx {
00014
00033 template <typename T>
00034 constexpr T gcd(T a, T b)
00035 {
00036     static_assert(Type_traits<T>::is_unsigned, "Type must be unsigned");
00037
00038     while (b != 0)
00039     {
00040         T remainder = a % b;
00041         a = b;
00042         b = remainder;
00043     }
00044
00045     return a;
00046 }
00047
00067 template <typename T>
00068 constexpr T lcm(T a, T b)
00069 {
00070     static_assert(Type_traits<T>::is_unsigned, "Type must be unsigned");
00071
00072     if (a == 0 || b == 0)
00073         return 0;
00074
00075     return (a / gcd(a, b)) * b;
00076 }
00077
00078 }

```

## 16.212 observer

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00002 /*
00003  * (c) 2010 Alexander Warg <warg@os.inf.tu-dresden.de>
00004  *     economic rights: Technische Universität Dresden (Germany)
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00008 #pragma once
00009
00010 #include <l4/cxx/hlist>
00011
00012 namespace cxx {
00013
00014 class Observer : public H_list_item
00015 {
00016 public:
00017     virtual void notify() = 0;
00018 };
00019
00020 class Notifier : public H_list<Observer>
00021 {
00022 public:
00023     void notify()
00024     {
00025         for (Iterator i = begin(); i != end(); ++i)
00026             i->notify();
00027     }
00028 };
00029
00030 }
00031
00032


```

## 16.213 l4/cxx/pair File Reference


Pair implementation.

```
#include <l4/cxx/type_traits>
```

Include dependency graph for pair:



This graph shows which files directly or indirectly include this file:



### Data Structures

- struct `cxx::Pair< First, Second >`  
*Pair of two values.*
- class `cxx::Pair_first_compare< Cmp, Typ >`  
*Comparison functor for [Pair](#).*

## Namespaces

- namespace [cxx](#)  
*Our C++ library.*

## 16.213.1 Detailed Description

Pair implementation.

Definition in file [pair](#).

## 16.214 [pair](#)

[Go to the documentation of this file.](#)

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00006 /*
00007  * (c) 2008-2009 Alexander Warg <warg@os.inf.tu-dresden.de>
00008  *      economic rights: Technische Universität Dresden (Germany)
00009  *
00010  * License: see LICENSE.spdx (in this directory or the directories above)
00011  */
00012 #pragma once
00013
00014 #include <l4/cxx/type_traits>
00015
00016 namespace cxx {
00017
00026 template< typename First, typename Second >
00027 struct Pair
00028 {
00030     typedef First First_type;
00032     typedef Second Second_type;
00033
00035     First first;
00037     Second second;
00038
00044     template<typename A1, typename A2>
00045     Pair(A1 &&first, A2 &&second)
00046     : first(cxx::forward<A1>(first)), second(cxx::forward<A2>(second)) {}
00047
00052     template<typename A1>
00053     Pair(A1 &&first)
00054     : first(cxx::forward<A1>(first)), second() {}
00055
00057     Pair() = default;
00058 };
00059
00060 template< typename F, typename S >
00061 Pair<F,S> pair(F const &f, S const &s)
00062 { return cxx::Pair<F,S>(f,s); }
00063
00064
00073 template< typename Cmp, typename Typ >
00074 class Pair_first_compare
00075 {
00076 private:
00077     Cmp const &_cmp;
00078
00079 public:
00084     Pair_first_compare(Cmp const &cmp = Cmp()) : _cmp(cmp) {}
00085
00091     bool operator () (Typ const &l, Typ const &r) const
00092     { return _cmp(l.first,r.first); }
00093 };
00094
00095 }
00096
00097 template< typename OS, typename A, typename B >
00098 inline
00099 OS &operator << (OS &os, cxx::Pair<A,B> const &p)
00100 {
00101     os << p.first << ' ' << p.second;
00102     return os;
00103 }
00104

```

## 16.215 ref\_ptr

```

00001 // vim:set ft=cpp: -*- Mode: C++ -*-
00002 /*
00003  * (c) 2008-2009 Alexander Warg <warg@os.inf.tu-dresden.de>
00004  *      economic rights: Technische Universität Dresden (Germany)
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00008
00009 #pragma once
00010
00011 #include "type_traits"
00012 #include <stddef.h>
00013 #include <14/sys/compiler.h>
00014
00015 namespace cxx {
00016
00017 template< typename T >
00018 struct Default_ref_counter
00019 {
00020     void h_drop_ref(T *p) noexcept
00021     {
00022         if (p->remove_ref() == 0)
00023             delete p;
00024     }
00025
00026     void h_take_ref(T *p) noexcept
00027     {
00028         p->add_ref();
00029     }
00030 };
00031
00032 struct Ref_ptr_base
00033 {
00034     enum Default_value
00035     { Nil = 0 };
00036 };
00037
00038 template<typename T, template< typename X > class CNT = Default_ref_counter>
00039 class Weak_ptr;
00040
00066 template <
00067     typename T = void,
00068     template< typename X > class CNT = Default_ref_counter
00069 >
00070 class Ref_ptr : public Ref_ptr_base, private CNT<T>
00071 {
00072 private:
00073     typedef decltype(nullptr) Null_type;
00074     typedef Weak_ptr<T, CNT> Wp;
00075
00076 public:
00077     Ref_ptr() noexcept : _p(0) {}
00078
00080     Ref_ptr(Ref_ptr_base::Default_value v)
00081     : _p(reinterpret_cast<T*>(static_cast<unsigned long>(v))) {}
00082
00088     Ref_ptr(Wp const &o) noexcept : _p(o.ptr())
00089     { __take_ref(); }
00090
00092     Ref_ptr(decltype(nullptr) n) noexcept : _p(n) {}
00093
00100     template<typename X>
00101     explicit Ref_ptr(X *o) noexcept : _p(o)
00102     { __take_ref(); }
00103
00114     Ref_ptr(T *o, [[maybe_unused]] bool d) noexcept : _p(o) { }
00115
00121     T *get() const noexcept
00122     {
00123         return _p;
00124     }
00125
00127     T *ptr() const noexcept
00128     {
00129         return _p;
00130     }
00131
00138     T *release() noexcept
00139     {
00140         T *p = _p;
00141         _p = 0;
00142         return p;
00143     }
00144

```

```

00145 ~Ref_ptr() noexcept
00146 { __drop_ref(); }
00147
00148 template<typename OT>
00149 Ref_ptr(Ref_ptr<OT, CNT> const &o) noexcept
00150 {
00151     _p = o.ptr();
00152     __take_ref();
00153 }
00154
00155 Ref_ptr(Ref_ptr<T> const &o) noexcept
00156 {
00157     _p = o._p;
00158     __take_ref();
00159 }
00160
00161 template< typename OT >
00162 void operator = (Ref_ptr<OT> const &o) noexcept
00163 {
00164     __drop_ref();
00165     _p = o.ptr();
00166     __take_ref();
00167 }
00168
00169 void operator = (Ref_ptr<T> const &o) noexcept
00170 {
00171     if (&o == this)
00172         return;
00173
00174     __drop_ref();
00175     _p = o._p;
00176     __take_ref();
00177 }
00178
00179 void operator = (Null_type) noexcept
00180 {
00181     __drop_ref();
00182     _p = 0;
00183 }
00184
00185 template<typename OT>
00186 Ref_ptr(Ref_ptr<OT, CNT> &&o) noexcept
00187 { _p = o.release(); }
00188
00189 Ref_ptr(Ref_ptr<T> &&o) noexcept
00190 { _p = o.release(); }
00191
00192 template< typename OT >
00193 void operator = (Ref_ptr<OT> &&o) noexcept
00194 {
00195     __drop_ref();
00196     _p = o.release();
00197 }
00198
00199 void operator = (Ref_ptr<T> &&o) noexcept
00200 {
00201     if (&o == this)
00202         return;
00203
00204     __drop_ref();
00205     _p = o.release();
00206 }
00207
00208 [[nodiscard]] explicit operator bool () const noexcept { return _p; }
00209
00210 T *operator -> () const noexcept
00211 { return _p; }
00212
00213 [[nodiscard]] bool operator == (Ref_ptr const &o) const noexcept
00214 { return _p == o._p; }
00215
00216 [[nodiscard]] bool operator != (Ref_ptr const &o) const noexcept
00217 { return _p != o._p; }
00218
00219 [[nodiscard]] bool operator < (Ref_ptr const &o) const noexcept
00220 { return _p < o._p; }
00221
00222 [[nodiscard]] bool operator <= (Ref_ptr const &o) const noexcept
00223 { return _p <= o._p; }
00224
00225 [[nodiscard]] bool operator > (Ref_ptr const &o) const noexcept
00226 { return _p > o._p; }
00227
00228 [[nodiscard]] bool operator >= (Ref_ptr const &o) const noexcept
00229 { return _p >= o._p; }
00230
00231 [[nodiscard]] bool operator == (T const *o) const noexcept

```

```

00232     { return _p == o; }
00233
00234     [[nodiscard]] bool operator < (T const *o) const noexcept
00235     { return _p < o; }
00236
00237     [[nodiscard]] bool operator <= (T const *o) const noexcept
00238     { return _p <= o; }
00239
00240     [[nodiscard]] bool operator > (T const *o) const noexcept
00241     { return _p > o; }
00242
00243     [[nodiscard]] bool operator >= (T const *o) const noexcept
00244     { return _p >= o; }
00245
00246 private:
00247     void __drop_ref() noexcept
00248     {
00249         if (_p)
00250             static_cast<CNT<T*>>(this)->h_drop_ref(_p);
00251     }
00252
00253     void __take_ref() noexcept
00254     {
00255         if (_p)
00256             static_cast<CNT<T*>>(this)->h_take_ref(_p);
00257     }
00258
00259     T *_p;
00260 };
00261
00262
00263 template<typename T, template< typename X > class CNT>
00264 class Weak_ptr
00265 {
00266 private:
00267     struct Null_type;
00268     typedef Ref_ptr<T, CNT> Rp;
00269
00270 public:
00271     Weak_ptr() = default;
00272     Weak_ptr(decltype(nullptr)) : _p(nullptr) {}
00273     // backwards 0 ctor
00274     explicit Weak_ptr(int x) noexcept
00275     L4_DEPRECATED("Use initialization from 'nullptr'")
00276     : _p(nullptr)
00277     { if (x != 0) __builtin_trap(); }
00278
00279     Weak_ptr(Rp const &o) noexcept : _p(o.ptr()) {}
00280     explicit Weak_ptr(T *o) noexcept : _p(o) {}
00281
00282     template<typename OT>
00283     Weak_ptr(Weak_ptr<OT, CNT> const &o) noexcept : _p(o.ptr()) {}
00284
00285     Weak_ptr(Weak_ptr<T, CNT> const &o) noexcept : _p(o._p) {}
00286
00287     Weak_ptr<T, CNT> &operator = (const Weak_ptr<T, CNT> &o) = default;
00288
00289     T *get() const noexcept { return _p; }
00290     T *ptr() const noexcept { return _p; }
00291
00292     T *operator -> () const noexcept { return _p; }
00293     operator Null_type const * () const noexcept
00294     { return reinterpret_cast<Null_type const*>(_p); }
00295
00296 private:
00297     T *_p;
00298 };
00299
00300 template<typename OT, typename T> inline
00301 Ref_ptr<OT> ref_ptr_static_cast(Ref_ptr<T> const &o)
00302 { return ref_ptr(static_cast<OT*>(o.ptr())); }
00303
00304 template< typename T >
00305 inline Ref_ptr<T> ref_ptr(T *t)
00306 { return Ref_ptr<T>(t); }
00307
00308 template< typename T >
00309 inline Weak_ptr<T> weak_ptr(T *t)
00310 { return Weak_ptr<T>(t); }
00311
00312
00313 class Ref_obj
00314 {
00315 private:
00316     mutable int _ref_cnt;
00317
00318 public:

```

```

00319   Ref_obj() : _ref_cnt(0) {}
00320   void add_ref() const noexcept { ++_ref_cnt; }
00321   int remove_ref() const noexcept { return --_ref_cnt; }
00322 };
00323
00324 template< typename T, typename... Args >
00325 Ref_ptr<T>
00326 make_ref_obj(Args &&... args)
00327 { return cxx::Ref_ptr<T>(new T(cxx::forward<Args>(args)...)); }
00328
00329 template<typename T, typename U>
00330 Ref_ptr<T>
00331 dynamic_pointer_cast(Ref_ptr<U> const &p) noexcept
00332 {
00333     // our constructor from a naked pointer increments the counter
00334     return Ref_ptr<T>(dynamic_cast<T *>(p.get()));
00335 }
00336
00337 template<typename T, typename U>
00338 Ref_ptr<T>
00339 static_pointer_cast(Ref_ptr<U> const &p) noexcept
00340 {
00341     // our constructor from a naked pointer increments the counter
00342     return Ref_ptr<T>(static_cast<T *>(p.get()));
00343 }
00344
00345 }

```

## 16.216 l4/cxx/ref\_ptr\_list File Reference


Implementation of a list of ref-ptr-managed objects.

```

#include <l4/cxx/ref_ptr>
#include "bits/smart_ptr_list.h"

```

Include dependency graph for ref\_ptr\_list:





## Data Structures

- struct `cxx::Ref_obj_list_item< T >`  
*Item for list linked via `cxx::Ref_ptr` with default reference counting.*

## Namespaces

- namespace `cxx`  
*Our C++ library.*

## Typedefs

- template<typename T>  
using `cxx::Ref_ptr_list_item` = `Bits::Smart_ptr_list_item<T, cxx::Ref_ptr<T> >`  
*Item for list linked with `cxx::Ref_ptr`.*
- template<typename T>  
using `cxx::Ref_ptr_list` = `Bits::Smart_ptr_list<Ref_ptr_list_item<T> >`  
*Single-linked list where elements are connected via a `cxx::Ref_ptr`.*

### 16.216.1 Detailed Description

Implementation of a list of ref-ptr-managed objects.

Definition in file [ref\\_ptr\\_list](#).

## 16.217 ref\_ptr\_list

[Go to the documentation of this file.](#)

```
00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00002 /*
00003  * Copyright (C) 2018, 2022, 2024 Kernkonzept GmbH.
00004  * Author(s): Sarah Hoffmann <sarah.hoffmann@kernkonzept.com>
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00008 #pragma once
00009
00010 #include <l4/cxx/ref_ptr>
00011
00012 #include "bits/smart_ptr_list.h"
00013
00014 namespace cxx {
00015
00016 template <typename T>
00017 using Ref_ptr_list_item = Bits::Smart_ptr_list_item<T, cxx::Ref_ptr<T> >;
00018
00019 template <typename T>
00020 struct Ref_obj_list_item : public Ref_ptr_list_item<T>, public cxx::Ref_obj {};
00021
00022 template <typename T>
00023 using Ref_ptr_list = Bits::Smart_ptr_list<Ref_ptr_list_item<T> >;
00024
00025 }
```

## 16.218 slab\_alloc

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00002 /*
00003  * (c) 2008-2009 Alexander Warg <warg@os.inf.tu-dresden.de>,
00004  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00005  *      economic rights: Technische Universität Dresden (Germany)
00006  *
00007  * License: see LICENSE.spdx (in this directory or the directories above)
00008  */
00009
00010 #pragma once
00011
00012 #include <l4/cxx/std_alloc>
00013 #include <l4/cxx/hlist>
00014 #include <l4/sys/consts.h>
00015
00016 namespace cxx {
00017
00029 template< int Obj_size, int Slab_size = L4_PAGESIZE,
00030          int Max_free = 2, template<typename A> class Alloc = New_allocator >
00031 class Base_slab
00032 {
00033 private:
00034     struct Free_o
00035     {
00036         Free_o *next;
00037     };
00038
00039 protected:
00040     struct Slab_i;
00041
00042 private:
00043     struct Slab_head : public H_list_item
00044     {
00045         unsigned num_free;
00046         Free_o *free;
00050         Base_slab<Obj_size, Slab_size, Max_free, Alloc> *cache;
00051
00052         inline Slab_head() noexcept : num_free(0), free(0), cache(0)
00053         {}
00054     };
00055
00056     // In an empty or partially filled slab, each free object stores a pointer to
00057     // the next free object. Thus, the size of an object needs to be at least the
00058     // size of a pointer.
00059     static_assert(Obj_size >= sizeof(void *),
00060                   "Object size must be at least the size of a pointer.");
00061     static_assert(Obj_size <= Slab_size - sizeof(Slab_head),
00062                   "Object_size exceeds slab capability.");
00063
00064 public:
00065     enum
00066     {
00068         object_size      = Obj_size,
00070         slab_size        = Slab_size,
00072         objects_per_slab = (Slab_size - sizeof(Slab_head)) / object_size,
00074         max_free_slabs   = Max_free,
00075     };
00076
00077 protected:
00078     struct Slab_store
00079     {
00080         char _o[slab_size - sizeof(Slab_head)];
00081         Free_o *object(unsigned obj) noexcept
00082         { return reinterpret_cast<Free_o*>(_o + object_size * obj); }
00083     };
00084
00086     struct Slab_i : public Slab_store, public Slab_head
00087     {};
00088
00089 public:
00091     typedef Alloc<Slab_i> Slab_alloc;
00092
00093     typedef void Obj_type;
00094
00095 private:
00097     Slab_alloc _alloc;
00099     unsigned _num_free;
00101     unsigned _num_slabs;
00103     H_list<Slab_i> _full_slabs;
00105     H_list<Slab_i> _partial_slabs;
00107     H_list<Slab_i> _empty_slabs;
00108
00110     void add_slab(Slab_i *s) noexcept
00111     {

```

```

00112     s->num_free = objects_per_slab;
00113     s->cache = this;
00114
00115     //L4::cerr << "Slab: " << this << "->add_slab(" << s << ", size="
00116     // << slab_size << "):" << " f=" << s->object(0) << '\n';
00117
00118     // initialize free list
00119     Free_o *f = s->free = s->object(0);
00120     for (unsigned i = 1; i < objects_per_slab; ++i)
00121     {
00122         f->next = s->object(i);
00123         f = f->next;
00124     }
00125     f->next = 0;
00126
00127     // insert slab into cache's list
00128     _empty_slabs.push_front(s);
00129     ++_num_slabs;
00130     ++_num_free;
00131 }
00132
00133 bool grow() noexcept
00134 {
00135     Slab_i *s = _alloc.alloc();
00136     if (!s)
00137         return false;
00138
00139     new (s, cxx::Nothrow()) Slab_i();
00140
00141     add_slab(s);
00142     return true;
00143 }
00144
00145 void shrink() noexcept
00146 {
00147     if (!_alloc.can_free)
00148         return;
00149
00150     while (!_empty_slabs.empty() && _num_free > max_free_slabs)
00151     {
00152         Slab_i *s = _empty_slabs.front();
00153         _empty_slabs.remove(s);
00154         --_num_free;
00155         --_num_slabs;
00156         _alloc.free(s);
00157     }
00158 }
00159
00160 public:
00161     Base_slab(Slab_alloc const &alloc = Slab_alloc()) noexcept
00162     : _alloc(alloc), _num_free(0), _num_slabs(0), _full_slabs(),
00163       _partial_slabs(), _empty_slabs()
00164     {}
00165
00166     ~Base_slab() noexcept
00167     {
00168         while (!_empty_slabs.empty())
00169         {
00170             Slab_i *o = _empty_slabs.front();
00171             _empty_slabs.remove(o);
00172             _alloc.free(o);
00173         }
00174         while (!_partial_slabs.empty())
00175         {
00176             Slab_i *o = _partial_slabs.front();
00177             _partial_slabs.remove(o);
00178             _alloc.free(o);
00179         }
00180         while (!_full_slabs.empty())
00181         {
00182             Slab_i *o = _full_slabs.front();
00183             _full_slabs.remove(o);
00184             _alloc.free(o);
00185         }
00186     }
00187
00188     void *alloc() noexcept
00189     {
00190         H_list<Slab_i> *free = &_partial_slabs;
00191         if (free->empty())
00192             free = &_empty_slabs;
00193
00194         if (free->empty() && !grow())
00195             return 0;
00196
00197         Slab_i *s = free->front();
00198         Free_o *o = s->free;

```

```

00218     s->free = o->next;
00219
00220     if (free == &_empty_slabs)
00221     {
00222         _empty_slabs.remove(s);
00223         --_num_free;
00224     }
00225
00226     --(s->num_free);
00227
00228     if (!s->free)
00229     {
00230         _partial_slabs.remove(s);
00231         _full_slabs.push_front(s);
00232     }
00233     else if (free == &_empty_slabs)
00234         _partial_slabs.push_front(s);
00235
00236     //L4::cerr << this << "->alloc(): " << o << ", of " << s << '\n';
00237
00238     return o;
00239 }
00240
00246 void free(void *_o) noexcept
00247 {
00248     if (!_o)
00249         return;
00250
00251     unsigned long addr = reinterpret_cast<unsigned long>(_o);
00252
00253     // find out the slab the object is in
00254     addr = (addr / slab_size) * slab_size;
00255     Slab_i *s = reinterpret_cast<Slab_i*>(addr);
00256
00257     if (s->cache != this)
00258         return;
00259
00260     Free_o *o = reinterpret_cast<Free_o*>(_o);
00261
00262     o->next = s->free;
00263     s->free = o;
00264
00265     bool was_full = false;
00266
00267     if (!s->num_free)
00268     {
00269         _full_slabs.remove(s);
00270         was_full = true;
00271     }
00272
00273     ++(s->num_free);
00274
00275     if (s->num_free == objects_per_slab)
00276     {
00277         if (!was_full)
00278             _partial_slabs.remove(s);
00279
00280         _empty_slabs.push_front(s);
00281         ++_num_free;
00282         if (_num_free > max_free_slabs)
00283             shrink();
00284
00285         was_full = false;
00286     }
00287     else if (was_full)
00288         _partial_slabs.push_front(s);
00289
00290     //L4::cerr << this << "->free(" << _o << "): of " << s << '\n';
00291 }
00292
00299 unsigned total_objects() const noexcept
00300 { return _num_slabs * objects_per_slab; }
00301
00308 unsigned free_objects() const noexcept
00309 {
00310     unsigned count = 0;
00311
00312     /* count partial slabs first */
00313     for (typename H_list<Slab_i>::Const_iterator s = _partial_slabs.begin();
00314          s != _partial_slabs.end(); ++s)
00315         count += s->num_free;
00316
00317     /* add empty slabs */
00318     count += _num_free * objects_per_slab;
00319
00320     return count;
00321 }

```

```

00322 };
00323
00333 template<typename Type, int Slab_size = L4_PAGESIZE,
00334         int Max_free = 2, template<typename A> class Alloc = New_allocator >
00335 class Slab : public Base_slab<sizeof(Type), Slab_size, Max_free, Alloc>
00336 {
00337 private:
00338     typedef Base_slab<sizeof(Type), Slab_size, Max_free, Alloc> Base_type;
00339 public:
00340
00341     typedef Type Obj_type;
00342
00343     Slab(typename Base_type::Slab_alloc const &alloc
00344         = typename Base_type::Slab_alloc()) noexcept
00345         : Base_slab<sizeof(Type), Slab_size, Max_free, Alloc>(alloc) {}
00346
00347
00355     Type *alloc() noexcept
00356     {
00357         return reinterpret_cast<Type *>(Base_type::alloc());
00358     }
00359
00366     void free(Type *o) noexcept
00367     { Base_slab<sizeof(Type), Slab_size, Max_free, Alloc>::free(o); }
00368 };
00369
00370
00386 template< int Obj_size, int Slab_size = L4_PAGESIZE,
00387         int Max_free = 2, template<typename A> class Alloc = New_allocator >
00388 class Base_slab_static
00389 {
00390 private:
00391     typedef Base_slab<Obj_size, Slab_size, Max_free, Alloc> _A;
00392     static _A _a;
00393 public:
00394     typedef void Obj_type;
00395     enum
00396     {
00398         object_size      = Obj_size,
00400         slab_size        = Slab_size,
00402         objects_per_slab = _A::objects_per_slab,
00404         max_free_slabs   = Max_free,
00405     };
00406
00412     void *alloc() noexcept { return _a.alloc(); }
00413
00420     void free(void *p) noexcept { _a.free(p); }
00421
00430     unsigned total_objects() const noexcept { return _a.total_objects(); }
00431
00440     unsigned free_objects() const noexcept { return _a.free_objects(); }
00441 };
00442
00443
00444 template< int _O, int _S, int _M, template<typename A> class Alloc >
00445 typename Base_slab_static<_O, _S, _M, Alloc>::_A
00446     Base_slab_static<_O, _S, _M, Alloc>::_a;
00447
00463 template<typename Type, int Slab_size = L4_PAGESIZE,
00464         int Max_free = 2, template<typename A> class Alloc = New_allocator >
00465 class Slab_static
00466 : public Base_slab_static<sizeof(Type), Slab_size, Max_free, Alloc>
00467 {
00468 public:
00469
00470     typedef Type Obj_type;
00478     Type *alloc() noexcept
00479     {
00480         return reinterpret_cast<Type *>(
00481             Base_slab_static<sizeof(Type), Slab_size, Max_free, Alloc>::alloc());
00482     }
00483 };
00484
00485 }

```

## 16.219 slist

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00002 /*
00003  * (c) 2011 Alexander Warg <warg@os.inf.tu-dresden.de>
00004  *     economic rights: Technische Universität Dresden (Germany)
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)

```

```

00007  */
00008
00009 #pragma once
00010
00011 #include "bits/list_basics.h"
00012
00013 namespace cxx {
00014
00015 class S_list_item
00016 {
00017 public:
00018     S_list_item() : _n(nullptr) {}
00019     // BSS allocation
00020     explicit S_list_item(bool) {}
00021
00022 private:
00023     template<typename T, typename P> friend class S_list;
00024     template<typename T, typename P> friend class S_list_tail;
00025     template<typename T, typename X> friend struct Bits::Basic_list_policy;
00026
00027     S_list_item(S_list_item const &);
00028     void operator = (S_list_item const &);
00029
00030     S_list_item *_n;
00031 };
00032
00033 template< typename T, typename POLICY = Bits::Basic_list_policy< T, S_list_item > >
00040 class S_list : public Bits::Basic_list<POLICY>
00041 {
00042     S_list(S_list const &) = delete;
00043     void operator = (S_list const &) = delete;
00044 private:
00045     typedef typename Bits::Basic_list<POLICY> Base;
00046 public:
00047     typedef typename Base::Iterator Iterator;
00048
00049     S_list(S_list &&o) : Base(static_cast<Base&&>(o)) {}
00050
00051     S_list &operator = (S_list &&o)
00052     {
00053         Base::operator = (static_cast<Base&&>(o));
00054         return *this;
00055     }
00056
00057     // BSS allocation
00058     explicit S_list(bool x) : Base(x) {}
00059
00060     S_list() : Base() {}
00061
00062     void add(T *e)
00063     {
00064         e->_n = this->_f;
00065         this->_f = e;
00066     }
00067
00068     template< typename CAS >
00069     void add(T *e, CAS const &c)
00070     {
00071         do
00072         {
00073             e->_n = this->_f;
00074         }
00075         while (!c(&this->_f, e->_n, e));
00076     }
00077
00078     void push_front(T *e) { add(e); }
00079
00080     T *pop_front()
00081     {
00082         T *r = this->front();
00083         if (this->_f)
00084             this->_f = this->_f->_n;
00085         return r;
00086     }
00087
00088     void insert(T *e, Iterator const &pred)
00089     {
00090         S_list_item *p = *pred;
00091         e->_n = p->_n;
00092         p->_n = e;
00093     }
00094
00095     static void insert_before(T *e, Iterator const &succ)
00096     {
00097         S_list_item **x = Base::__get_internal(succ);

```

```

00107
00108     e->_n = *x;
00109     *x = e;
00110 }
00111
00112 static void replace(Iterator const &p, T*e)
00113 {
00114     S_list_item **x = Base::__get_internal(p);
00115     e->_n = (*x)->_n;
00116     *x = e;
00117 }
00118
00119 static Iterator erase(Iterator const &e)
00120 {
00121     S_list_item **x = Base::__get_internal(e);
00122     *x = (*x)->_n;
00123     return e;
00124 }
00125
00126 };
00127
00128
00129 template< typename T >
00130 class S_list_bss : public S_list<T>
00131 {
00132 public:
00133     S_list_bss() : S_list<T>(true) {}
00134 };
00135
00136 template< typename T, typename POLICY = Bits::Basic_list_policy< T, S_list_item > >
00137 class S_list_tail : public S_list<T, POLICY>
00138 {
00139 private:
00140     typedef S_list<T, POLICY> Base;
00141     void add(T *e) = delete;
00142
00143 public:
00144     using Iterator = typename Base::Iterator;
00145     S_list_tail() : Base(), _tail(&this->_f) {}
00146
00147     S_list_tail(S_list_tail &&t)
00148     : Base(static_cast<Base&&>(t)), _tail(t.empty() ? &this->_f : t._tail)
00149     {
00150         t._tail = &t._f;
00151     }
00152
00153     S_list_tail &operator = (S_list_tail &&t)
00154     {
00155         if (&t == this)
00156             return *this;
00157
00158         Base::operator = (static_cast<Base&&>(t));
00159         _tail = t.empty() ? &this->_f : t._tail;
00160         t._tail = &t._f;
00161         return *this;
00162     }
00163
00164     void push_front(T *e)
00165     {
00166         if (Base::empty())
00167             _tail = &e->_n;
00168
00169         Base::push_front(e);
00170     }
00171
00172     void push_back(T *e)
00173     {
00174         e->_n = nullptr;
00175         *_tail = e;
00176         _tail = &e->_n;
00177     }
00178
00179     void clear()
00180     {
00181         Base::clear();
00182         _tail = &this->_f;
00183     }
00184
00185     void append(S_list_tail &o)
00186     {
00187         T *x = o.front();
00188         *_tail = x;
00189         if (x)
00190             _tail = o._tail;
00191         o.clear();
00192     }
00193

```

```

00194     T *pop_front()
00195     {
00196         T *t = Base::pop_front();
00197         if (t && Base::empty())
00198             _tail = &this->_f;
00199         return t;
00200     }
00201
00202 private:
00203     static void insert(T *e, Iterator const &pred);
00204     static void insert_before(T *e, Iterator const &succ);
00205     static void replace(Iterator const &p, T*e);
00206     static Iterator erase(Iterator const &e);
00207
00208 private:
00209     S_list_item **_tail;
00210 };
00211
00212 }

```

## 16.220 static\_container

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00002 /*
00003  * Copyright (C) 2012-2013 Technische Universität Dresden.
00004  * Copyright (C) 2016-2017, 2020, 2023-2024 Kernkonzept GmbH.
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00008
00009 #pragma once
00010
00011 #include <l4/cxx/type_traits>
00012 #include <stddef.h>
00013
00014 namespace cxx {
00015
00016 template< typename T >
00017 class Static_container
00018 {
00019 private:
00020     struct X : T
00021     {
00022         void *operator new (size_t, void *p) noexcept { return p; }
00023         void operator delete (void *) {}
00024         X() = default;
00025         template<typename ...Args>
00026         X(Args && ...a) : T(cxx::forward<Args>(a)...) {}
00027     };
00028
00029 public:
00030     void operator = (Static_container const &) = delete;
00031     Static_container(Static_container const &) = delete;
00032     Static_container() = default;
00033
00034     T *get() { return reinterpret_cast<X*>(_s); }
00035     T *operator -> () { return get(); }
00036     T &operator * () { return *get(); }
00037     operator T* () { return get(); }
00038
00039     void construct()
00040     { new (reinterpret_cast<void*>(_s)) X; }
00041
00042     template< typename ...Args >
00043     void construct(Args && ...args)
00044     { new (reinterpret_cast<void*>(_s)) X(cxx::forward<Args>(args)...); }
00045
00046 private:
00047     char _s[sizeof(X)] __attribute__((aligned(__alignof(X))));
00048 };
00049
00050 }
00051
00052

```

## 16.221 static\_vector

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-

```



```

00002
00003 #pragma once
00004
00005 #include "type_traits"
00006
00007 namespace cxx {
00008
00009 template<typename T, typename IDX = unsigned>
00010 class static_vector
00011 {
00012 private:
00013     template<typename X, typename IDX2> friend class static_vector;
00014     T *_v;
00015     IDX _l;
00016
00017 public:
00018     typedef T value_type;
00019     typedef IDX index_type;
00020
00021     static_vector() = default;
00022     static_vector(value_type *v, index_type length) : _v(v), _l(length) {}
00023
00024     template<typename Z,
00025             typename = enable_if_t<is_same<remove_extent_t<Z>, T>::value>
00026     constexpr static_vector(Z &v) : _v(v), _l(array_size(v))
00027     {}
00028
00029     template<typename X,
00030             typename = enable_if_t<is_convertible<X, T>::value>
00031     static_vector(static_vector<X, IDX> const &o) : _v(o._v), _l(o._l) {}
00032
00033     index_type size() const { return _l; }
00034     bool empty() const { return _l == 0; }
00035
00036     value_type &operator [] (index_type idx) { return _v[idx]; }
00037     value_type const &operator [] (index_type idx) const { return _v[idx]; }
00038
00039     value_type *begin() { return _v; }
00040     value_type *end() { return _v + _l; }
00041     value_type const *begin() const { return _v; }
00042     value_type const *end() const { return _v + _l; }
00043     value_type const *cbegin() const { return _v; }
00044     value_type const *cend() const { return _v + _l; }
00045
00046     index_type index(value_type const *o) const { return o - _v; }
00047     index_type index(value_type const &o) const { return &o - _v; }
00048 };
00049
00050 }

```

## 16.222 std\_alloc

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00002 /*
00003  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00004  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00005  *      economic rights: Technische Universität Dresden (Germany)
00006  *
00007  * License: see LICENSE.spdx (in this directory or the directories above)
00008  */
00009
00010 #pragma once
00011
00012 #include <stddef.h>
00013 namespace cxx {
00014 class Nothrow {};
00015
00016 inline void *operator new (size_t, void *mem, cxx::Nothrow const &) noexcept
00017 { return mem; }
00018
00019 void *operator new (size_t, cxx::Nothrow const &) noexcept;
00020
00021 void operator delete (void *, cxx::Nothrow const &) noexcept;
00022
00023 namespace cxx {
00024
00025     template< typename _Type >
00026     class New_allocator
00027     {
00028     public:
00029         enum { can_free = true };

```

```

00060
00061 New_allocator() noexcept {}
00062 New_allocator(New_allocator const &) noexcept {}
00063
00064 ~New_allocator() noexcept {}
00065
00066 _Type *alloc() noexcept
00067 { return static_cast<_Type*> (::operator new(sizeof (_Type), cxx::Nothrow())); }
00068
00069 void free(_Type *t) noexcept
00070 { ::operator delete(t, cxx::Nothrow()); }
00071 };
00072
00073 }
00074

```

## 16.223 std\_ops

```

00001 // vim:set ft=cpp: -*- Mode: C++ -*-
00002 /*
00003  * (c) 2008-2009 Alexander Warg <warg@os.inf.tu-dresden.de>,
00004  *      Torsten Frenzel <frenzel@os.inf.tu-dresden.de>
00005  *      economic rights: Technische Universität Dresden (Germany)
00006  *
00007  * License: see LICENSE.spdx (in this directory or the directories above)
00008  */
00009
00010 #pragma once
00011
00012 namespace cxx {
00013
00014 template< typename Obj >
00015 struct Lt_functor
00016 {
00017     bool operator () (Obj const &l, Obj const &r) const
00018     { return l < r; }
00019 };
00020
00021 };
00022
00023
00024 };
00025

```

## 16.224 string

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00002 /*
00003  * (c) 2008-2009 Alexander Warg <warg@os.inf.tu-dresden.de>
00004  *      economic rights: Technische Universität Dresden (Germany)
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00008
00009 #pragma once
00010
00011 #include <l4/cxx/minmax>
00012 #include <l4/cxx/basic_ostream>
00013
00014 namespace cxx {
00015
00016 class String
00017 {
00018 public:
00019     typedef char const *Index;
00020
00021     String(char const *s) noexcept : _start(s), _len(__builtin_strlen(s)) {}
00022     String(char const *s, unsigned long len) noexcept : _start(s), _len(len) {}
00023
00024     String(char const *s, char const *e) noexcept : _start(s), _len(e - s) {}
00025
00026     String() : _start(0), _len(0) {}
00027
00028     Index start() const { return _start; }
00029     Index end() const { return _start + _len; }
00030     int len() const { return _len; }
00031
00032     void start(char const *s) { _start = s; }
00033     void len(unsigned long len) { _len = len; }
00034

```

```

00065 bool empty() const { return !_len; }
00066
00068 String head(Index end) const
00069 {
00070     if (end < _start)
00071         return String();
00072
00073     if (eof(end))
00074         return *this;
00075
00076     return String(_start, end - _start);
00077 }
00078
00080 String head(unsigned long end) const
00081 { return head(start() + end); }
00082
00084 String substr(unsigned long idx, unsigned long len = ~0UL) const
00085 {
00086     if (idx >= _len)
00087         return String(end(), 0UL);
00088
00089     return String(_start + idx, cxx::min(len, _len - idx));
00090 }
00091
00093 String substr(char const *start, unsigned long len = 0) const
00094 {
00095     if (start >= _start && !eof(start))
00096     {
00097         unsigned long nlen = _start + _len - start;
00098         if (len != 0)
00099             nlen = cxx::min(nlen, len);
00100         return String(start, nlen);
00101     }
00102
00103     return String(end(), 0UL);
00104 }
00105
00107 template< typename F >
00108 char const *find_match(F &&match) const
00109 {
00110     String::Index s = _start;
00111     while (1)
00112     {
00113         if (eof(s))
00114             return s;
00115
00116         if (match(*s))
00117             return s;
00118
00119         ++s;
00120     }
00121 }
00122
00124 char const *find(char const *c) const
00125 { return find(c, start()); }
00126
00128 char const *find(int c) const
00129 { return find(c, start()); }
00130
00132 char const *rfind(char const *c) const
00133 {
00134     if (!_len)
00135         return end();
00136
00137     char const *p = end();
00138     --p;
00139     while (p >= _start)
00140     {
00141         if (*p == *c)
00142             return p;
00143         --p;
00144     }
00145     return end();
00146 }
00147
00148
00155 Index starts_with(cxx::String const &c) const
00156 {
00157     unsigned long i;
00158     for (i = 0; i < c._len && i < _len; ++i)
00159         if (_start[i] != c[i])
00160             return 0;
00161     return i == c._len ? start() + i : 0;
00162 }
00163
00165 char const *find(int c, char const *s) const
00166 {

```

```

00167     if (s < _start)
00168         return end();
00169
00170     while (1)
00171     {
00172     if (eof(s))
00173         return s;
00174
00175     if (*s == c)
00176         return s;
00177
00178     ++s;
00179     }
00180 }
00181
00191 char const *find(char const *c, char const *s) const
00192 {
00193     if (s < _start)
00194         return end();
00195
00196     while (1)
00197     {
00198     if (eof(s))
00199         return s;
00200
00201     for (char const *x = c; *x; ++x)
00202         if (*s == *x)
00203             return s;
00204
00205     ++s;
00206     }
00207 }
00208
00210 char const &operator [] (unsigned long idx) const { return _start[idx]; }
00212 char const &operator [] (int idx) const { return _start[idx]; }
00214 char const &operator [] (Index idx) const { return *idx; }
00215
00217 bool eof(char const *s) const { return s >= _start + _len || !*s; }
00218
00227 template<typename INT>
00228 int from_dec(INT *v) const
00229 {
00230     *v = 0;
00231     Index c;
00232     for (c = start(); !eof(c); ++c)
00233     {
00234         unsigned char n;
00235         if (*c >= '0' && *c <= '9')
00236             n = *c - '0';
00237         else
00238             return c - start();
00239
00240         *v *= 10;
00241         *v += n;
00242     }
00243     return c - start();
00244 }
00245
00256 template<typename INT>
00257 int from_hex(INT *v) const
00258 {
00259     *v = 0;
00260     unsigned shift = 0;
00261     Index c;
00262     for (c = start(); !eof(c); ++c)
00263     {
00264         shift += 4;
00265         if (shift > sizeof(INT) * 8)
00266             return -1;
00267         unsigned char n;
00268         if (*c >= '0' && *c <= '9')
00269             n = *c - '0';
00270         else if (*c >= 'A' && *c <= 'F')
00271             n = *c - 'A' + 10;
00272         else if (*c >= 'a' && *c <= 'f')
00273             n = *c - 'a' + 10;
00274         else
00275             return c - start();
00276
00277         *v <<= 4;
00278         *v |= n;
00279     }
00280     return c - start();
00281 }
00282
00284 bool operator == (String const &o) const
00285 {

```

```

00286     if (len() != o.len())
00287         return false;
00288
00289     for (unsigned long i = 0; i < _len; ++i)
00290         if (_start[i] != o._start[i])
00291             return false;
00292
00293     return true;
00294 }
00295
00296 bool operator != (String const &o) const
00297 { return ! (operator == (o)); }
00298
00299 private:
00300     char const *_start;
00301     unsigned long _len;
00302 };
00303
00304 inline
00305 L4::BasicOStream &operator << (L4::BasicOStream &s, cxx::String const &str)
00306 {
00307     s.write(str.start(), str.len());
00308     return s;
00309 }


```

## 16.225 l4/cxx/string.h File Reference


String.

```
#include <l4/cxx/basic_ostream>
```

Include dependency graph for string.h:



This graph shows which files directly or indirectly include this file:



## Data Structures

- class [L4::String](#)

*A null-terminated string container class.*

## Namespaces

- namespace [L4](#)

*[L4](#) low-level kernel interface.*

## 16.225.1 Detailed Description

String.

Definition in file [string.h](#).

## 16.226 string.h

[Go to the documentation of this file.](#)

```

00001
00005 /*
00006  * (c) 2004-2009 Alexander Warg <warg@os.inf.tu-dresden.de>,
00007  *      Torsten Frenzel <frenzel@os.inf.tu-dresden.de>
00008  *      economic rights: Technische Universität Dresden (Germany)
00009  *
00010  * License: see LICENSE.spdx (in this directory or the directories above)
00011  */
00012 #pragma once
00013
00014 #include <l4/cxx/basic_ostream>
00015
00016 namespace L4 {
00017
00022 class String
00023 {
00024 public:
00025     String(char const *str = "") : _str(str)
00026     {}
00027
00028     unsigned length() const
00029     {
00030         unsigned l;
00031         for (l = 0; _str[l]; l++)
00032             ;
00033         return l;
00034     }
00035
00036     char const *p_str() const { return _str; }
00037
00038 private:
00039     char const *_str;
00040 };
00041
00042
00043 inline
00044 L4::BasicOStream &operator << (L4::BasicOStream &o, L4::String const &s)
00045 {
00046     o << s.p_str();
00047     return o;
00048 }

```

## 16.227 type\_list

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00002 #pragma once
00003
00004 /*
00005  * (c) 2012 Alexander Warg <warg@os.inf.tu-dresden.de>,
00006  *      economic rights: Technische Universität Dresden (Germany)
00007  *
00008  * License: see LICENSE.spdx (in this directory or the directories above)
00009  */
00010
00011
00012 #include "type_traits"
00013
00014 namespace cxx {
00015
00016 template< typename ...T >
00017 struct type_list;
00018
00019 template<>
00020 struct type_list<>
00021 {
00022     typedef false_type head;
00023     typedef false_type tail;
00024 };
00025
00026 template<typename HEAD, typename ...TAIL>
00027 struct type_list<HEAD, TAIL...>
00028 {
00029     typedef HEAD head;
00030     typedef type_list<TAIL...> tail;
00031 };
00032
00033 template<typename TYPELIST, template <typename T> class PREDICATE>
00034 struct find_type;
00035
00036 template<template <typename T> class PREDICATE>
00037 struct find_type<type_list<>, PREDICATE>
00038 {
00039     typedef false_type type;
00040 };
00041
00042 template<typename TYPELIST, template <typename T> class PREDICATE>
00043 struct find_type
00044 {
00045     typedef typename conditional<PREDICATE<typename TYPELIST::head>::value,
00046                               typename TYPELIST::head,
00047                               typename find_type<typename TYPELIST::tail, PREDICATE>::type>::type
00048     type;
00049 };
00050
00051 template<typename TYPELIST, template <typename T> class PREDICATE>
00052 using find_type_t = typename find_type<TYPELIST, PREDICATE>::type;
00053 }

```

## 16.228 type\_traits

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00002
00003 /*
00004  * (c) 2008-2009 Alexander Warg <warg@os.inf.tu-dresden.de>,
00005  *      Torsten Frenzel <frenzel@os.inf.tu-dresden.de>
00006  *      economic rights: Technische Universität Dresden (Germany)
00007  *
00008  * License: see LICENSE.spdx (in this directory or the directories above)
00009  */
00010
00011
00012 #pragma once
00013
00014 #pragma GCC system_header
00015
00016 #include <14/sys/compiler.h>
00017 #include "bits/type_traits.h"
00018
00019 namespace cxx {
00020
00021 template< typename T, T V >
00022 struct integral_constant
00023 {

```

```

00024     static T const value = V;
00025     typedef T value_type;
00026     typedef integral_constant<T, V> type;
00027 };
00028
00029 typedef integral_constant<bool, true> true_type;
00030 typedef integral_constant<bool, false> false_type;
00031
00032 template<typename...>
00033 using void_t = void;
00034
00035 template< typename T > struct remove_reference;
00036
00037 template< typename T > struct identity { typedef T type; };
00038 template< typename T > using identity_t = typename identity<T>::type;
00039
00040 template< typename T1, typename T2 > struct is_same;
00041
00042 template< typename T > struct remove_const;
00043
00044 template< typename T > struct remove_volatile;
00045
00046 template< typename T > struct remove_cv;
00047
00048 template< typename T > struct remove_pointer;
00049
00050 template< typename T > struct remove_extent;
00051
00052 template< typename T > struct remove_all_extents;
00053
00054
00055
00056 template< typename, typename >
00057 struct is_same : false_type {};
00058
00059 template< typename T >
00060 struct is_same<T, T> : true_type {};
00061
00062 template< typename T1, typename T2 >
00063 inline constexpr bool is_same_v = is_same<T1, T2>::value;
00064
00065 template< typename T >
00066 struct remove_reference { typedef T type; };
00067
00068 template< typename T >
00069 struct remove_reference<T &> { typedef T type; };
00070
00071 template< typename T >
00072 struct remove_reference<T &&> { typedef T type; };
00073
00074 template< typename T >
00075 using remove_reference_t = typename remove_reference<T>::type;
00076
00077 template< typename T > struct remove_const { typedef T type; };
00078 template< typename T > struct remove_const<T const> { typedef T type; };
00079 template< typename T > using remove_const_t = typename remove_const<T>::type;
00080
00081 template< typename T > struct remove_volatile { typedef T type; };
00082 template< typename T > struct remove_volatile<T volatile> { typedef T type; };
00083 template< typename T > using remove_volatile_t = typename remove_volatile<T>::type;
00084
00085 template< typename T >
00086 struct remove_cv { typedef remove_const_t<remove_volatile_t<T> type; };
00087
00088 template< typename T >
00089 using remove_cv_t = typename remove_cv<T>::type;
00090
00091 template<class T>
00092 struct remove_cvref { using type = remove_cv_t<remove_reference_t<T> }; };
00093
00094 template< typename T >
00095 using remove_cvref_t = typename remove_cvref<T>::type;
00096
00097 template< typename T, typename >
00098 struct __remove_pointer_h { typedef T type; };
00099
00100 template< typename T, typename I >
00101 struct __remove_pointer_h<T, I*> { typedef I type; };
00102
00103 template< typename T >
00104 struct remove_pointer : __remove_pointer_h<T, remove_cv_t<T> {};
00105
00106 template< typename T >
00107 using remove_pointer_t = typename remove_pointer<T>::type;
00108
00109
00110 template< typename T >

```



```

00111 struct remove_extent { typedef T type; };
00112
00113 template< typename T >
00114 struct remove_extent<T[]> { typedef T type; };
00115
00116 template< typename T, unsigned long N >
00117 struct remove_extent<T[N]> { typedef T type; };
00118
00119 template< typename T >
00120 using remove_extent_t = typename remove_extent<T>::type;
00121
00122
00123 template< typename T >
00124 struct remove_all_extents { typedef T type; };
00125
00126 template< typename T >
00127 struct remove_all_extents<T[]> { typedef typename remove_all_extents<T>::type type; };
00128
00129 template< typename T, unsigned long N >
00130 struct remove_all_extents<T[N]> { typedef typename remove_all_extents<T>::type type; };
00131
00132 template< typename T >
00133 using remove_all_extents_t = typename remove_all_extents<T>::type;
00134
00135 template< typename T >
00136 constexpr T &&
00137 forward(cxx::remove_reference_t<T> &t)
00138 { return static_cast<T &&>(t); }
00139
00140 template< typename T >
00141 constexpr T &&
00142 forward(cxx::remove_reference_t<T> &&t)
00143 { return static_cast<T &&>(t); }
00144
00145 template< typename T >
00146 constexpr cxx::remove_reference_t<T> &&
00147 move(T &&t) { return static_cast<cxx::remove_reference_t<T> &&>(t); }
00148
00149 template< bool, typename T = void >
00150 struct enable_if {};
00151
00152 template< typename T >
00153 struct enable_if<true, T> { typedef T type; };
00154
00155 template< bool C, typename T = void >
00156 using enable_if_t = typename enable_if<C, T>::type;
00157
00158 template< typename T >
00159 struct is_const : false_type {};
00160
00161 template< typename T >
00162 struct is_const<T const> : true_type {};
00163
00164 template< typename T >
00165 inline constexpr bool is_const_v = is_const<T>::value;
00166
00167 template< typename T >
00168 struct is_volatile : false_type {};
00169
00170 template< typename T >
00171 struct is_volatile<T volatile> : true_type {};
00172
00173 template< typename T >
00174 inline constexpr bool is_volatile_v = is_volatile<T>::value;
00175
00176 template< typename T >
00177 struct is_pointer : false_type {};
00178
00179 template< typename T >
00180 struct is_pointer<T *> : true_type {};
00181
00182 template< typename T >
00183 inline constexpr bool is_pointer_v = is_pointer<T>::value;
00184
00185 template<class T>
00186 inline constexpr bool is_null_pointer_v = is_same_v<decltype(nullptr), remove_cv_t<T>>;
00187
00188 template< typename T >
00189 struct is_reference : false_type {};
00190
00191 template< typename T >
00192 struct is_reference<T &> : true_type {};
00193
00194 template< typename T >
00195 struct is_reference<T &&> : true_type {};
00196
00197 template< typename T >

```

```

00198 inline constexpr bool is_reference_v = is_reference<T>::value;
00199
00200 template< bool, typename, typename >
00201 struct conditional;
00202
00203 template< bool C, typename T_TRUE, typename T_FALSE >
00204 struct conditional { typedef T_TRUE type; };
00205
00206 template< typename T_TRUE, typename T_FALSE >
00207 struct conditional< false, T_TRUE, T_FALSE > { typedef T_FALSE type; };
00208
00209 template< bool C, typename T_TRUE, typename T_FALSE >
00210 using conditional_t = typename conditional<C, T_TRUE, T_FALSE>::type;
00211
00212 template<typename T>
00213 struct is_enum : integral_constant<bool, __is_enum(T)> {};
00214
00215 template< typename T >
00216 inline constexpr bool is_enum_v = is_enum<T>::value;
00217
00218 template<typename T>
00219 struct is_polymorphic : cxx::integral_constant<bool, __is_polymorphic(T)> {};
00220
00221 template< typename T > struct is_integral : false_type {};
00222
00223 template<> struct is_integral<bool> : true_type {};
00224
00225 template<> struct is_integral<char> : true_type {};
00226 template<> struct is_integral<signed char> : true_type {};
00227 template<> struct is_integral<unsigned char> : true_type {};
00228 template<> struct is_integral<short> : true_type {};
00229 template<> struct is_integral<unsigned short> : true_type {};
00230 template<> struct is_integral<int> : true_type {};
00231 template<> struct is_integral<unsigned int> : true_type {};
00232 template<> struct is_integral<long> : true_type {};
00233 template<> struct is_integral<unsigned long> : true_type {};
00234 template<> struct is_integral<long long> : true_type {};
00235 template<> struct is_integral<unsigned long long> : true_type {};
00236
00237 template< typename T >
00238 inline constexpr bool is_integral_v = is_integral<T>::value;
00239
00240 template< typename T, bool = is_integral_v<T> || is_enum_v<T> >
00241 struct __is_signed_helper : integral_constant<bool, static_cast<bool>(T(-1) < T(0))> {};
00242
00243 template< typename T >
00244 struct __is_signed_helper<T, false> : integral_constant<bool, false> {};
00245
00246 template< typename T >
00247 struct is_signed : __is_signed_helper<T> {};
00248
00249 template< typename T >
00250 inline constexpr bool is_signed_v = is_signed<T>::value;
00251
00252
00253 template< typename >
00254 struct is_array : false_type {};
00255
00256 template< typename T >
00257 struct is_array<T[]> : true_type {};
00258
00259 template< typename T, unsigned long N >
00260 struct is_array<T[N]> : true_type {};
00261
00262 template< typename T >
00263 inline constexpr bool is_array_v = is_array<T>::value;
00264
00265 template< typename T, unsigned N >
00266 constexpr unsigned array_size(T const (&)[N]) { return N; }
00267
00268 template< int SIZE, bool SIGN = false, bool = true > struct int_type_for_size;
00269
00270 template<> struct int_type_for_size<sizeof(char), true, true>
00271 { typedef signed char type; };
00272
00273 template<> struct int_type_for_size<sizeof(char), false, true>
00274 { typedef unsigned char type; };
00275
00276 template<> struct int_type_for_size<sizeof(short), true, (sizeof(short) > sizeof(char))>
00277 { typedef short type; };
00278
00279 template<> struct int_type_for_size<sizeof(short), false, (sizeof(short) > sizeof(char))>
00280 { typedef unsigned short type; };
00281
00282 template<> struct int_type_for_size<sizeof(int), true, (sizeof(int) > sizeof(short))>
00283 { typedef int type; };
00284

```

```

00285 template<> struct int_type_for_size<sizeof(int), false, (sizeof(int) > sizeof(short))>
00286 { typedef unsigned int type; };
00287
00288 template<> struct int_type_for_size<sizeof(long), true, (sizeof(long) > sizeof(int))>
00289 { typedef long type; };
00290
00291 template<> struct int_type_for_size<sizeof(long), false, (sizeof(long) > sizeof(int))>
00292 { typedef unsigned long type; };
00293
00294 template<> struct int_type_for_size<sizeof(long long), true, (sizeof(long long) > sizeof(long))>
00295 { typedef long long type; };
00296
00297 template<> struct int_type_for_size<sizeof(long long), false, (sizeof(long long) > sizeof(long))>
00298 { typedef unsigned long long type; };
00299
00300 template< int SIZE, bool SIGN = false>
00301 using int_type_for_size_t = typename int_type_for_size<SIZE, SIGN>::type;
00302
00303 template< typename T, class Enable = void > struct underlying_type {};
00304
00305 template< typename T >
00306 struct underlying_type<T, typename enable_if<is_enum_v<T>::type >
00307 {
00308     typedef int_type_for_size_t<sizeof(T), is_signed_v<T> type;
00309 };
00310
00311 template< typename T >
00312 using underlying_type_t = typename underlying_type<T>::type;
00313
00314 template< typename T > struct make_signed;
00315 template<> struct make_signed<char> { typedef signed char type; };
00316 template<> struct make_signed<unsigned char> { typedef signed char type; };
00317 template<> struct make_signed<signed char> { typedef signed char type; };
00318 template<> struct make_signed<unsigned int> { typedef signed int type; };
00319 template<> struct make_signed<signed int> { typedef signed int type; };
00320 template<> struct make_signed<unsigned long int> { typedef signed long int type; };
00321 template<> struct make_signed<signed long int> { typedef signed long int type; };
00322 template<> struct make_signed<unsigned long long int> { typedef signed long long int type; };
00323 template<> struct make_signed<signed long long int> { typedef signed long long int type; };
00324 template< typename T > using make_signed_t = typename make_signed<T>::type;
00325
00326 template< typename T > struct make_unsigned;
00327 template<> struct make_unsigned<char> { typedef unsigned char type; };
00328 template<> struct make_unsigned<unsigned char> { typedef unsigned char type; };
00329 template<> struct make_unsigned<signed char> { typedef unsigned char type; };
00330 template<> struct make_unsigned<unsigned int> { typedef unsigned int type; };
00331 template<> struct make_unsigned<signed int> { typedef unsigned int type; };
00332 template<> struct make_unsigned<unsigned long int> { typedef unsigned long int type; };
00333 template<> struct make_unsigned<signed long int> { typedef unsigned long int type; };
00334 template<> struct make_unsigned<unsigned long long int> { typedef unsigned long long int type; };
00335 template<> struct make_unsigned<signed long long int> { typedef unsigned long long int type; };
00336 template< typename T > using make_unsigned_t = typename make_unsigned<T>::type;
00337
00338
00339 template<typename From, typename To>
00340 struct is_convertible
00341 {
00342 private:
00343     struct _true { char x[2]; };
00344     struct _false {};
00345
00346     static _true _helper(To const *);
00347     static _false _helper(...);
00348 public:
00349     enum
00350     {
00351         value = sizeof(_true) == sizeof(_helper(static_cast<From*>(0)))
00352             ? true : false
00353     };
00354
00355     typedef bool value_type;
00356 };
00357
00358 template<typename From, typename To>
00359 inline constexpr bool is_convertible_v = is_convertible<From, To>::value;
00360
00361 template< typename T >
00362 struct is_empty : integral_constant<bool, __is_empty(T)> {};
00363
00364 template< typename T >
00365 inline constexpr bool is_empty_v = is_empty<T>::value;
00366
00367
00368 #if L4_HAS_BUILTIN(__is_function)
00369     template < typename T >
00370     struct is_function : integral_constant<bool, __is_function(T)> {};
00371 #else

```

```

00372     template < typename T >
00373     struct is_function : integral_constant<bool,      !is_reference_v<T>
00374                                     && !is_const_v<const T> {}> {};
00375 #endif
00376
00377 template< typename T >
00378 inline constexpr bool is_function_v = is_function<T>::value;
00379
00380 }
00381

```

## 16.229 unique\_ptr

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00002 /*
00003  * Copyright (C) 2013      Technische Universität Dresden.
00004  * Copyright (C) 2014-2017, 2020, 2023-2024 Kernkonzept GmbH.
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00008
00009 #pragma once
00010
00011 #include "type_traits"
00012
00013 namespace cxx
00014 {
00015
00016     template< typename T >
00017     struct default_delete
00018     {
00019         default_delete() {}
00020
00021         template< typename U >
00022         default_delete(default_delete<U> const &) {}
00023
00024         void operator () (T *p) const
00025         { delete p; }
00026     };
00027
00028     template< typename T >
00029     struct default_delete<T[]>
00030     {
00031         default_delete() {}
00032
00033         void operator () (T *p)
00034         { delete [] p; }
00035     };
00036
00037     template< typename T, typename C >
00038     struct unique_ptr_index_op {};
00039
00040     template< typename T, typename C >
00041     struct unique_ptr_index_op<T[], C>
00042     {
00043         typedef T &reference;
00044         reference operator [] (int idx) const
00045         { return static_cast<C const *>(this)->get()[idx]; }
00046     };
00047
00048     template< typename T, typename T_Del = default_delete<T> >
00049     class unique_ptr : public unique_ptr_index_op<T, unique_ptr<T, T_Del> >
00050     {
00051     private:
00052         struct _unspec;
00053         typedef _unspec* _unspec_ptr_type;
00054
00055     public:
00056         typedef cxx::remove_extent_t<T> element_type;
00057         typedef element_type *pointer;
00058         typedef element_type &reference;
00059         typedef T_Del deleter_type;
00060
00061         unique_ptr() : _ptr(pointer()) {}
00062
00063         explicit unique_ptr(pointer p) : _ptr(p) {}
00064
00065         unique_ptr(unique_ptr &&o) : _ptr(o.release()) {}
00066
00067         ~unique_ptr() { reset(); }
00068
00069         unique_ptr &operator = (unique_ptr &&o)
00070         {

```

```

00071     reset(o.release());
00072     return *this;
00073 }
00074
00075 unique_ptr &operator = (_unspec_ptr_type)
00076 {
00077     reset();
00078     return *this;
00079 }
00080
00081 element_type &operator * () const { return *get(); }
00082 pointer operator -> () const { return get(); }
00083
00084 pointer get() const { return _ptr; }
00085
00086 operator _unspec_ptr_type () const
00087 { return reinterpret_cast<_unspec_ptr_type>(get()); }
00088
00089 pointer release()
00090 {
00091     pointer r = _ptr;
00092     _ptr = 0;
00093     return r;
00094 }
00095
00096 void reset(pointer p = pointer())
00097 {
00098     if (p != get())
00099     {
00100         deleter_type()(get());
00101         _ptr = p;
00102     }
00103 }
00104
00105 unique_ptr(unique_ptr const &) = delete;
00106 unique_ptr &operator = (unique_ptr const &) = delete;
00107
00108 private:
00109     pointer _ptr;
00110 };
00111
00112 template< typename T >
00113 unique_ptr<T>
00114 make_unique_ptr(T *p)
00115 { return unique_ptr<T>(p); }
00116
00117 template< typename T >
00118 cxx::enable_if_t< cxx::is_array<T>::value, unique_ptr<T> >
00119 make_unique(unsigned long size)
00120 { return cxx::unique_ptr<T>(new cxx::remove_extent_t<T>[size]()); }
00121
00122 template< typename T, typename... Args >
00123 cxx::enable_if_t< !cxx::is_array<T>::value, unique_ptr<T> >
00124 make_unique(Args &&... args)
00125 { return cxx::unique_ptr<T>(new T(cxx::forward<Args>(args)...)); }
00126
00127 }

```

## 16.230 l4/cxx/unique\_ptr\_list File Reference


Implementation of a list of unique\_ptr-managed objects.

```

#include <l4/cxx/unique_ptr>
#include "bits/smart_ptr_list.h"

```

Include dependency graph for `unique_ptr_list`:



## Namespaces

- namespace `cxx`  
*Our C++ library.*

## Typedefs

- `template<typename T>`  
using `cxx::Unique_ptr_list_item` = `Bits::Smart_ptr_list_item`<T, `cxx::unique_ptr`<T> >  
*Item for list linked with `cxx::unique_ptr`.*
- `template<typename T>`  
using `cxx::Unique_ptr_list` = `Bits::Smart_ptr_list`<`Unique_ptr_list_item`<T> >  
*Single-linked list where elements are connected with a `cxx::unique_ptr`.*

### 16.230.1 Detailed Description

Implementation of a list of unique-ptr-managed objects.

Definition in file `unique_ptr_list`.

## 16.231 unique\_ptr\_list

[Go to the documentation of this file.](#)

```
00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00002 /*
00003  * Copyright (C) 2018-2019, 2022, 2024 Kernkonzept GmbH.
00004  * Author(s): Sarah Hoffmann <sarah.hoffmann@kernkonzept.com>
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00008 #pragma once
00009
00010 #include <l4/cxx/unique_ptr>
00011
00012 #include "bits/smart_ptr_list.h"
00013
00014 namespace cxx {
00015
00016 template <typename T>
00017 using Unique_ptr_list_item = Bits::Smart_ptr_list_item<T, cxx::unique_ptr<T> >;
00018
00019 template <typename T>
00020 using Unique_ptr_list = Bits::Smart_ptr_list<Unique_ptr_list_item<T> >;
00021
00022 }
```

## 16.232 utils

```
00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00002 /*
00003  * Copyright (C) 2013 Technische Universität Dresden.
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007 #pragma once
00008
00009 namespace cxx {
00010
00011 template< typename T > inline
00012 T access_once(T const *a)
00013 {
00014     if 1
00015         __asm__ __volatile__ ( "" : "=m"(*const_cast<T*>(a));
00016                                T tmp = *a;
00017                                __asm__ __volatile__ ( "" : "=m"(*const_cast<T*>(a));
00018                                return tmp;
00019     else
00020         return *static_cast<T const volatile *>(a);
00021     #endif
00022 }
00023
00024 template< typename T, typename VAL > inline
00025 void write_now(T *a, VAL &&val)
00026 {
00027     __asm__ __volatile__ ( "" : "=m"(*a);
00028                            *a = val;
00029                            __asm__ __volatile__ ( "" : : "m"(*a));
00030 }
00031
00032 }
```

## 16.233 weak\_ref

```
00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00002 /*
00003  * Copyright (C) 2015, 2017, 2024 Kernkonzept GmbH.
00004  * Author(s): Sarah Hoffmann <sarah.hoffmann@kernkonzept.com>
00005  *            Alexander Warg <alexander.warg@kernkonzept.com>
00006  *
00007  * License: see LICENSE.spdx (in this directory or the directories above)
00008  */
00009 #pragma once
```

```

00010
00011 #include "hlist"
00012
00013 namespace cxx {
00014
00024 class Weak_ref_base : public H_list_item_t<Weak_ref_base>
00025 {
00026 protected:
00027     Weak_ref_base(void const *ptr = nullptr) : _obj(ptr) {}
00028     void reset_hard() { _obj = nullptr; }
00029     void const *_obj;
00030
00031 public:
00038     struct List : H_list_t<Weak_ref_base>
00039     {
00040         void reset()
00041         {
00042             while (!empty())
00043                 pop_front()->reset_hard();
00044         }
00045
00046         ~List()
00047         { reset(); }
00048     };
00049
00050     explicit operator bool () const
00051     { return _obj ? true : false; }
00052 };
00053
00054
00094 template <typename T>
00095 class Weak_ref : public Weak_ref_base
00096 {
00097 public:
00098     T *get() const
00099     { return reinterpret_cast<T*>(const_cast<void *>(_obj)); }
00100
00101     T *reset(T *n)
00102     {
00103         T *r = get();
00104         if (r)
00105             r->remove_weak_ref(this);
00106
00107         _obj = n;
00108         if (n)
00109             n->add_weak_ref(this);
00110
00111         return r;
00112     }
00113
00114     Weak_ref(T *s = nullptr) : Weak_ref_base(s)
00115     {
00116         if (s)
00117             s->add_weak_ref(this);
00118     }
00119
00120     ~Weak_ref() { reset(0); }
00121
00122     void operator = (T *n)
00123     { reset(n); }
00124
00125     Weak_ref(Weak_ref const &o) : Weak_ref_base(o._obj)
00126     {
00127         if (T *x = get())
00128             x->add_weak_ref(this);
00129     }
00130
00131     Weak_ref &operator = (Weak_ref const &o)
00132     {
00133         if (&o == this)
00134             return *this;
00135
00136         reset(o.get());
00137         return *this;
00138     }
00139
00140     T &operator * () const { return get(); }
00141     T *operator -> () const { return get(); }
00142 };
00143
00144 class Weak_ref_obj
00145 {
00146 protected:
00147     template <typename T> friend class Weak_ref;
00148     mutable Weak_ref_base::List weak_references;
00149
00150     void add_weak_ref(Weak_ref_base *ref) const

```




```
00151 { weak_references.push_front(ref); }
00152
00153 void remove_weak_ref(Weak_ref_base *ref) const
00154 { weak_references.remove(ref); }
00155 };
00156
00157 }
```

## 16.234 amd64/l4/util/irq.h File Reference

some PIC and hardware interrupt related functions

```
#include <l4/sys/compiler.h>
#include <l4/util/port_io.h>
Include dependency graph for irq.h:
```



### 16.234.1 Detailed Description

some PIC and hardware interrupt related functions

#### Date

2003

#### Author

Jork Loeser [jork.loeser@inf.tu-dresden.de](mailto:jork.loeser@inf.tu-dresden.de) Frank Mehnert [fm3@os.inf.tu-dresden.de](mailto:fm3@os.inf.tu-dresden.de)

Definition in file [irq.h](#).

## 16.235 irq.h


[Go to the documentation of this file.](#)

```
00001
00008
00009 /*
00010  * (c) 2003-2009 Author(s)
00011  *     economic rights: Technische Universität Dresden (Germany)
00012  * License: see LICENSE.spdx (in this directory or the directories above)
00013  */
00014
00015 #ifndef __L4_IRQ_H__
00016 #define __L4_IRQ_H__
00017
00018 #include <l4/sys/compiler.h>
00019 #include <l4/util/port_io.h>
00020
00021 L4_BEGIN_DECLS
00022
00027
00030 static inline void
00031 l4util_cli (void)
00032 {
00033     __asm__ __volatile__ ("cli" : : : "memory");
00034 }
00035
00038 static inline void
00039 l4util_sti (void)
00040 {
00041     __asm__ __volatile__ ("sti" : : : "memory");
00042 }
00043
00047 static inline void
00048 l4util_flags_save (l4_umword_t *flags)
00049 {
00050     __asm__ __volatile__ ("pushf ; popq %0" : "=g" (*flags) : : "memory");
00051 }
00052
00055 static inline void
00056 l4util_flags_restore (l4_umword_t *flags)
00057 {
00058     __asm__ __volatile__ ("pushq %0 ; popf" : : "g" (*flags) : "memory");
00059 }
00061
00062 L4_END_DECLS
00063
00064 #endif
```

## 16.236 arm/l4/util/irq.h File Reference

ARM specific implementation of irq functions.

```
#include <l4/sys/compiler.h>
Include dependency graph for irq.h:
```



### 16.236.1 Detailed Description

ARM specific implementation of irq functions.

Do not use.

Definition in file [irq.h](#).

## 16.237 irq.h

[Go to the documentation of this file.](#)

```

00001
00007 /*
00008  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00009  *               Alexander Warg <warg@os.inf.tu-dresden.de>,
00010  *               Frank Mehnert <fm3@os.inf.tu-dresden.de>
00011  *               economic rights: Technische Universität Dresden (Germany)
00012  * License: see LICENSE.spdx (in this directory or the directories above)
00013  */
00014 #ifndef __L4UTIL__ARCH_ARCH__IRQ_H__
00015 #define __L4UTIL__ARCH_ARCH__IRQ_H__
00016
00017 #ifdef __GNUC__
00018
00019 #include <l4/sys/compiler.h>
00020
00021 L4_BEGIN_DECLS
00022
00023 L4_INLINE void l4util_cli (void);
00024 L4_INLINE void l4util_sti (void);
00025 L4_INLINE void l4util_flags_save(l4_umword_t *flags);
00026 L4_INLINE void l4util_flags_restore(l4_umword_t *flags);
00027
00028 L4_INLINE
00029 void
00030 l4util_cli(void)
00031 {
00032     extern void __do_not_use_l4util_cli(void);
00033     __do_not_use_l4util_cli();
00034 }
00035

```

```

00036
00037 L4_INLINE
00038 void
00039 l4util_sti(void)
00040 {
00041     extern void __do_not_use_l4util_sti(void);
00042     __do_not_use_l4util_sti();
00043 }
00044
00045
00046 L4_INLINE
00047 void
00048 l4util_flags_save(l4_umword_t *flags)
00049 {
00050     (void) flags;
00051     extern void __do_not_use_l4util_flags_save(void);
00052     __do_not_use_l4util_flags_save();
00053 }
00054
00055 L4_INLINE
00056 void
00057 l4util_flags_restore(l4_umword_t *flags)
00058 {
00059     (void) flags;
00060     extern void __do_not_use_l4util_flags_restore(void);
00061     __do_not_use_l4util_flags_restore();
00062 }
00063
00064 L4_END_DECLS
00065
00066 #endif // __GNUC__
00067
00068 #endif /* ! __L4UTIL__ARCH_ARCH__IRQ_H__ */

```


## 16.238 l4/irq/irq.h File Reference

IRQ handling routines.

```
#include <l4/sys/compiler.h>
```

```
#include <l4/sys/types.h>
```

Include dependency graph for irq.h:



### Functions

- `l4irq_t * l4irq_attach` (int irqnum)  
*Attach/connect to IRQ.*

- `l4irq_t * l4irq_attach_ft` (int irqnum, unsigned mode)  
*Attach/connect to IRQ using given type.*
- `l4irq_t * l4irq_attach_thread` (int irqnum, `l4_cap_idx_t` to\_thread)  
*Attach/connect to IRQ.*
- `l4irq_t * l4irq_attach_thread_ft` (int irqnum, `l4_cap_idx_t` to\_thread, unsigned mode)  
*Attach/connect to IRQ using given type.*
- `long l4irq_wait` (`l4irq_t *irq`)  
*Wait for specified IRQ.*
- `long l4irq_unmask_and_wait_any` (`l4irq_t *unmask_irq`, `l4irq_t **ret_irq`)  
*Unmask a specific IRQ and wait for any attached IRQ.*
- `long l4irq_wait_any` (`l4irq_t **irq`)  
*Wait for any attached IRQ.*
- `long l4irq_unmask` (`l4irq_t *irq`)  
*Unmask a specific IRQ.*
- `long l4irq_detach` (`l4irq_t *irq`)  
*Detach from IRQ.*
- `l4irq_t * l4irq_request` (int irqnum, `void(*isr_handler)(void *)`, `void *isr_data`, int irq\_thread\_prio, unsigned mode)  
*Attach asynchronous ISR handler to IRQ.*
- `long l4irq_release` (`l4irq_t *irq`)  
*Release asynchronous ISR handler and free resources.*
- `l4irq_t * l4irq_attach_cap` (`l4_cap_idx_t` irqcap)  
*Attach/connect to IRQ.*
- `l4irq_t * l4irq_attach_cap_ft` (`l4_cap_idx_t` irqcap, unsigned mode)  
*Attach/connect to IRQ using given type.*
- `l4irq_t * l4irq_attach_thread_cap` (`l4_cap_idx_t` irqcap, `l4_cap_idx_t` to\_thread)  
*Attach/connect to IRQ.*
- `l4irq_t * l4irq_attach_thread_cap_ft` (`l4_cap_idx_t` irqcap, `l4_cap_idx_t` to\_thread, unsigned mode)  
*Attach/connect to IRQ using given type.*
- `l4irq_t * l4irq_request_cap` (`l4_cap_idx_t` irqcap, `void(*isr_handler)(void *)`, `void *isr_data`, int irq\_thread\_↵prio, unsigned mode)  
*Attach asynchronous ISR handler to IRQ.*

### 16.238.1 Detailed Description

IRQ handling routines.

Definition in file [irq.h](#).

## 16.239 irq.h

[Go to the documentation of this file.](#)

```

00001
00005 /*
00006  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00007  *      Henning Schild <hschild@os.inf.tu-dresden.de>
00008  *      economic rights: Technische Universität Dresden (Germany)
00009  *
00010  * This file is part of TUD:OS and distributed under the terms of the
00011  * GNU General Public License 2.
00012  * Please see the COPYING-GPL-2 file for details.
00013  */
00014 #pragma once

```

```

00015
00016 #include <l4/sys/compiler.h>
00017 #include <l4/sys/types.h>
00018
00019 __BEGIN_DECLS
00020
00027
00028 struct l4irq_t;
00029 typedef struct l4irq_t l4irq_t;
00030
00041 L4_CV l4irq_t *
00042 l4irq_attach(int irqnum);
00043
00055 L4_CV l4irq_t *
00056 l4irq_attach_ft(int irqnum, unsigned mode);
00057
00068 L4_CV l4irq_t *
00069 l4irq_attach_thread(int irqnum, l4_cap_idx_t to_thread);
00070
00082 L4_CV l4irq_t *
00083 l4irq_attach_thread_ft(int irqnum, l4_cap_idx_t to_thread,
00084                        unsigned mode);
00085
00093 L4_CV long
00094 l4irq_wait(l4irq_t *irq);
00095
00105 L4_CV long
00106 l4irq_unmask_and_wait_any(l4irq_t *unmask_irq, l4irq_t **ret_irq);
00107
00115 L4_CV long
00116 l4irq_wait_any(l4irq_t **irq);
00117
00128 L4_CV long
00129 l4irq_unmask(l4irq_t *irq);
00130
00138 L4_CV long
00139 l4irq_detach(l4irq_t *irq);
00140
00141
00142
00143 /*****
00152
00165 L4_CV l4irq_t *
00166 l4irq_request(int irqnum, void (*isr_handler)(void *), void *isr_data,
00167              int irq_thread_prio, unsigned mode);
00168
00176 L4_CV long
00177 l4irq_release(l4irq_t *irq);
00178
00179
00180
00181 /*****
00182 /*****
00183
00188
00199 L4_CV l4irq_t *
00200 l4irq_attach_cap(l4_cap_idx_t irqcap);
00201
00213 L4_CV l4irq_t *
00214 l4irq_attach_cap_ft(l4_cap_idx_t irqcap, unsigned mode);
00215
00226 L4_CV l4irq_t *
00227 l4irq_attach_thread_cap(l4_cap_idx_t irqcap, l4_cap_idx_t to_thread);
00228
00240 L4_CV l4irq_t *
00241 l4irq_attach_thread_cap_ft(l4_cap_idx_t irqcap, l4_cap_idx_t to_thread,
00242                             unsigned mode);
00243
00244 /*****
00252
00265 L4_CV l4irq_t *
00266 l4irq_request_cap(l4_cap_idx_t irqcap,
00267                  void (*isr_handler)(void *), void *isr_data,
00268                  int irq_thread_prio, unsigned mode);
00269
00270 __END_DECLS


```

## 16.240 l4/sys/irq.h File Reference


C Irq interface.

```
#include <l4/sys/kernel_object.h>
#include <l4/sys/ipc.h>
#include <l4/sys/rcv_endpoint.h>
```

Include dependency graph for irq.h:



This graph shows which files directly or indirectly include this file:



## Functions

- [l4\\_msgtag\\_t l4\\_irq\\_detach \(l4\\_cap\\_idx\\_t irq\) L4\\_NOTHROW](#)  
Detach from an interrupt source.
- [l4\\_msgtag\\_t l4\\_irq\\_detach\\_u \(l4\\_cap\\_idx\\_t irq, l4\\_utcb\\_t \\*utcb\) L4\\_NOTHROW](#)  
Detach from this interrupt.

- `l4_msgtag_t l4_irq_bind_vcpu (l4_cap_idx_t irq, l4_cap_idx_t thread, l4_umword_t cfg) L4_NOTHROW`  
*Bind a thread to this Irq for vCPU interrupt forwarding.*
- `l4_msgtag_t l4_irq_bind_vcpu_u (l4_cap_idx_t irq, l4_cap_idx_t thread, l4_umword_t cfg, l4_utcb_t *utcb) L4_NOTHROW`  
*Bind a thread to this Irq for vCPU interrupt forwarding.*
- `l4_msgtag_t l4_irq_trigger (l4_cap_idx_t irq) L4_NOTHROW`  
*Trigger an IRQ.*
- `l4_msgtag_t l4_irq_trigger_u (l4_cap_idx_t irq, l4_utcb_t *utcb) L4_NOTHROW`  
*Trigger the object.*
- `l4_msgtag_t l4_irq_receive (l4_cap_idx_t irq, l4_timeout_t to) L4_NOTHROW`  
*Unmask and wait for specified IRQ.*
- `l4_msgtag_t l4_irq_receive_u (l4_cap_idx_t irq, l4_timeout_t timeout, l4_utcb_t *utcb) L4_NOTHROW`  
*Unmask and wait for this IRQ.*
- `l4_msgtag_t l4_irq_wait (l4_cap_idx_t irq, l4_umword_t *label, l4_timeout_t to) L4_NOTHROW`  
*Unmask IRQ and wait for any message.*
- `l4_msgtag_t l4_irq_wait_u (l4_cap_idx_t irq, l4_umword_t *label, l4_timeout_t timeout, l4_utcb_t *utcb) L4_NOTHROW`  
*Unmask IRQ and (open) wait for any message.*
- `l4_msgtag_t l4_irq_unmask (l4_cap_idx_t irq) L4_NOTHROW`  
*Unmask IRQ.*
- `l4_msgtag_t l4_irq_unmask_u (l4_cap_idx_t irq, l4_utcb_t *utcb) L4_NOTHROW`  
*Unmask this IRQ.*

## 16.240.1 Detailed Description

C Irq interface.

Definition in file [irq.h](#).

## 16.241 irq.h

[Go to the documentation of this file.](#)

```

00001
00006 /*
00007  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00008  *                Alexander Warg <warg@os.inf.tu-dresden.de>,
00009  *                Björn Döbel <doebel@os.inf.tu-dresden.de>
00010  *                economic rights: Technische Universität Dresden (Germany)
00011  *
00012  * License: see LICENSE.spdx (in this directory or the directories above)
00013  */
00014 #pragma once
00015
00016 #include <l4/sys/kernel_object.h>
00017 #include <l4/sys/ipc.h>
00018 #include <l4/sys/rcv_endpoint.h>
00019
00046
00062 L4_INLINE l4_msgtag_t
00063 l4_irq_detach(l4_cap_idx_t irq) L4_NOTHROW;
00064
00071 L4_INLINE l4_msgtag_t
00072 l4_irq_detach_u(l4_cap_idx_t irq, l4_utcb_t *utcb) L4_NOTHROW;
00073
00074
00109 L4_INLINE l4_msgtag_t
00110 l4_irq_bind_vcpu(l4_cap_idx_t irq, l4_cap_idx_t thread,
00111                 l4_umword_t cfg) L4_NOTHROW;
00112
00119 L4_INLINE l4_msgtag_t

```



```

00120 l4_irq_bind_vcpu_u(l4_cap_idx_t irq, l4_cap_idx_t thread, l4_umword_t cfg,
00121                  l4_utcb_t *utcb) L4_NOTHROW;
00122
00123
00139 L4_INLINE l4_msgtag_t
00140 l4_irq_trigger(l4_cap_idx_t irq) L4_NOTHROW;
00141
00148 L4_INLINE l4_msgtag_t
00149 l4_irq_trigger_u(l4_cap_idx_t irq, l4_utcb_t *utcb) L4_NOTHROW;
00150
00160 L4_INLINE l4_msgtag_t
00161 l4_irq_receive(l4_cap_idx_t irq, l4_timeout_t to) L4_NOTHROW;
00162
00169 L4_INLINE l4_msgtag_t
00170 l4_irq_receive_u(l4_cap_idx_t irq, l4_timeout_t timeout, l4_utcb_t *utcb) L4_NOTHROW;
00171
00182 L4_INLINE l4_msgtag_t
00183 l4_irq_wait(l4_cap_idx_t irq, l4_umword_t *label,
00184            l4_timeout_t to) L4_NOTHROW;
00185
00192 L4_INLINE l4_msgtag_t
00193 l4_irq_wait_u(l4_cap_idx_t irq, l4_umword_t *label,
00194             l4_timeout_t timeout, l4_utcb_t *utcb) L4_NOTHROW;
00195
00206 L4_INLINE l4_msgtag_t
00207 l4_irq_unmask(l4_cap_idx_t irq) L4_NOTHROW;
00208
00215 L4_INLINE l4_msgtag_t
00216 l4_irq_unmask_u(l4_cap_idx_t irq, l4_utcb_t *utcb) L4_NOTHROW;
00217
00221 enum L4_irq_sender_op
00222 {
00223     L4_IRQ_SENDER_OP_RESERVED1 = 0, // Ex ATTACH
00224     L4_IRQ_SENDER_OP_DETACH    = 1,
00225     L4_IRQ_SENDER_OP_BIND_VCPU = 2,
00226 };
00227
00231 enum L4_irq_op
00232 {
00233     L4_IRQ_OP_TRIGGER    = 2,
00234     L4_IRQ_OP_EOI        = 4,
00235 };
00236
00237 /*****
00238  * Implementations
00239  */
00240
00241 L4_INLINE l4_msgtag_t
00242 l4_irq_detach_u(l4_cap_idx_t irq, l4_utcb_t *utcb) L4_NOTHROW
00243 {
00244     l4_utcb_mr_u(utcb)->mr[0] = L4_IRQ_SENDER_OP_DETACH;
00245     return l4_ipc_call(irq, utcb, l4_msgtag(L4_PROTO_IRQ_SENDER, 1, 0, 0),
00246                      L4_IPC_NEVER);
00247 }
00248
00249 L4_INLINE l4_msgtag_t
00250 l4_irq_bind_vcpu_u(l4_cap_idx_t irq, l4_cap_idx_t thread, l4_umword_t cfg,
00251                  l4_utcb_t *utcb) L4_NOTHROW
00252 {
00253     l4_msg_regs_t *m = l4_utcb_mr_u(utcb);
00254     m->mr[0] = L4_IRQ_SENDER_OP_BIND_VCPU;
00255     m->mr[1] = cfg;
00256     m->mr[2] = l4_map_obj_control(0, 0);
00257     m->mr[3] = l4_obj_fpage(thread, 0, L4_CAP_FPAGE_RWS).raw;
00258     return l4_ipc_call(irq, utcb, l4_msgtag(L4_PROTO_IRQ_SENDER, 2, 1, 0),
00259                      L4_IPC_NEVER);
00260 }
00261
00262 L4_INLINE l4_msgtag_t
00263 l4_irq_trigger_u(l4_cap_idx_t irq, l4_utcb_t *utcb) L4_NOTHROW
00264 {
00265     return l4_ipc_send(irq, utcb, l4_msgtag(L4_PROTO_IRQ, 0, 0, 0),
00266                      L4_IPC_BOTH_TIMEOUT_0);
00267 }
00268
00269 L4_INLINE l4_msgtag_t
00270 l4_irq_receive_u(l4_cap_idx_t irq, l4_timeout_t to, l4_utcb_t *utcb) L4_NOTHROW
00271 {
00272     l4_utcb_mr_u(utcb)->mr[0] = L4_IRQ_OP_EOI;
00273     return l4_ipc_call(irq, utcb, l4_msgtag(L4_PROTO_IRQ, 1, 0, 0), to);
00274 }
00275
00276 L4_INLINE l4_msgtag_t
00277 l4_irq_wait_u(l4_cap_idx_t irq, l4_umword_t *label,
00278             l4_timeout_t to, l4_utcb_t *utcb) L4_NOTHROW
00279 {
00280     l4_utcb_mr_u(utcb)->mr[0] = L4_IRQ_OP_EOI;

```

```

00281     return l4_ipc_send_and_wait(irq, utcb, l4_msgtag(L4_PROTO_IRQ, 1, 0, 0),
00282                                 label, to);
00283 }
00284
00285 L4_INLINE l4_msgtag_t
00286 l4_irq_unmask_u(l4_cap_idx_t irq, l4_utcb_t *utcb) L4_NOTHROW
00287 {
00288     l4_utcb_mr_u(utcb)->mr[0] = L4_IRQ_OP_EOI;
00289     return l4_ipc_send(irq, utcb, l4_msgtag(L4_PROTO_IRQ, 1, 0, 0), L4_IPC_NEVER);
00290 }
00291
00292
00293 L4_INLINE l4_msgtag_t
00294 l4_irq_detach(l4_cap_idx_t irq) L4_NOTHROW
00295 {
00296     return l4_irq_detach_u(irq, l4_utcb());
00297 }
00298
00299 L4_INLINE l4_msgtag_t
00300 l4_irq_bind_vcpu(l4_cap_idx_t irq, l4_cap_idx_t thread,
00301                 l4_umword_t cfg) L4_NOTHROW
00302 {
00303     return l4_irq_bind_vcpu_u(irq, thread, cfg, l4_utcb());
00304 }
00305
00306 L4_INLINE l4_msgtag_t
00307 l4_irq_trigger(l4_cap_idx_t irq) L4_NOTHROW
00308 {
00309     return l4_irq_trigger_u(irq, l4_utcb());
00310 }
00311
00312 L4_INLINE l4_msgtag_t
00313 l4_irq_receive(l4_cap_idx_t irq, l4_timeout_t to) L4_NOTHROW
00314 {
00315     return l4_irq_receive_u(irq, to, l4_utcb());
00316 }
00317
00318 L4_INLINE l4_msgtag_t
00319 l4_irq_wait(l4_cap_idx_t irq, l4_umword_t *label,
00320            l4_timeout_t to) L4_NOTHROW
00321 {
00322     return l4_irq_wait_u(irq, label, to, l4_utcb());
00323 }
00324
00325 L4_INLINE l4_msgtag_t
00326 l4_irq_unmask(l4_cap_idx_t irq) L4_NOTHROW
00327 {
00328     return l4_irq_unmask_u(irq, l4_utcb());
00329 }
00330

```

## 16.242 x86/I4/util/irq.h File Reference


some PIC and hardware interrupt related functions

```

#include <l4/sys/compiler.h>
#include <l4/util/port_io.h>

```

Include dependency graph for irq.h:



### 16.242.1 Detailed Description

some PIC and hardware interrupt related functions

Date

2003

Author

Jork Loeser [jork.loeser@inf.tu-dresden.de](mailto:jork.loeser@inf.tu-dresden.de) Frank Mehnert [fm3@os.inf.tu-dresden.de](mailto:fm3@os.inf.tu-dresden.de)

Definition in file [irq.h](#).

## 16.243 irq.h

[Go to the documentation of this file.](#)

```

00001
00008
00009 /*
00010  * (c) 2003-2009 Author(s)
00011  *     economic rights: Technische Universität Dresden (Germany)
00012  * License: see LICENSE.spdx (in this directory or the directories above)
00013  */
00014
00015 #ifndef __L4_IRQ_H__
00016 #define __L4_IRQ_H__
00017
00018 #include <l4/sys/compiler.h>
00019 #include <l4/util/port_io.h>
00020
00021 L4_BEGIN_DECLS
00022
00027
00030 static inline void
00031 l4util_cli (void)
00032 {

```

```

00033  __asm__ __volatile__ ("cli" : : : "memory");
00034 }
00035
00038 static inline void
00039 l4util_sti (void)
00040 {
00041  __asm__ __volatile__ ("sti" : : : "memory");
00042 }
00043
00047 static inline void
00048 l4util_flags_save (l4_umword_t *flags)
00049 {
00050  __asm__ __volatile__ ("pushfl ; popl %0" : "=g" (*flags) : : "memory");
00051 }
00052
00055 static inline void
00056 l4util_flags_restore (l4_umword_t *flags)
00057 {
00058  __asm__ __volatile__ ("pushl %0 ; popfl" : : "g" (*flags) : "memory");
00059 }
00061
00062 L4_END_DECLS
00063
00064 #endif

```

## 16.244 backend

```

00001 // vi:set ft=c++: -- Mode: C++ --
00002 /*
00003  * (c) 2010 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00004  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00005  *      economic rights: Technische Universität Dresden (Germany)
00006  *
00007  * License: see LICENSE.spdx (in this directory or the directories above)
00008  */
00009 #pragma once
00010
00011 #include <l4/l4re_vfs/vfs.h>
00012 #include <l4/crtn/initpriorities.h>
00013
00014 extern "C" void l4re_vfs_select_poll_notify(void);
00015
00016 namespace L4Re { namespace Vfs {
00017
00019 extern L4Re::Vfs::Ops *vfs_ops asm ("l4re_env_posix_vfs_ops");
00020
00021 class Mount_tree;
00022
00030 class Be_file : public File
00031 {
00032 public:
00033  void *operator new (size_t size) noexcept
00034  { return vfs_ops->malloc(size); }
00035
00036  void *operator new (size_t, void *m) noexcept
00037  { return m; }
00038
00039  void operator delete (void *m)
00040  { vfs_ops->free(m); }
00041
00042  // used in close, to unlock all locks of a file (as POSIX says)
00043  int unlock_all_locks() noexcept override
00044  { return 0; }
00045
00046  // for mmap
00047  L4::Cap<L4Re::Dataspace> data_space() noexcept override
00048  { return L4::Cap<L4Re::Dataspace>::Invalid; }
00049
00051 ssize_t readv(const struct iovec*, int) noexcept override
00052 { return -EINVAL; }
00053
00055 ssize_t writev(const struct iovec*, int) noexcept override
00056 { return -EINVAL; }
00057
00059 ssize_t pwritev(const struct iovec*, int, off64_t) noexcept override
00060 { return -EINVAL; }
00061
00063 ssize_t preadv(const struct iovec*, int, off64_t) noexcept override
00064 { return -EINVAL; }
00065
00067 off64_t lseek(off64_t, int) noexcept override
00068 { return -ESPIPE; }
00069

```

```

00071 int ftruncate(off64_t) noexcept override
00072 { return -EINVAL; }
00073
00075 int fsync() const noexcept override
00076 { return -EINVAL; }
00077
00079 int fdatasync() const noexcept override
00080 { return -EINVAL; }
00081
00083 int ioctl(unsigned long, va_list) noexcept override
00084 { return -EINVAL; }
00085
00086 int fstat(struct stat64 *) const noexcept override
00087 { return -EINVAL; }
00088
00090 int fchmod(mode_t) noexcept override
00091 { return -EINVAL; }
00092
00094 int get_status_flags() const noexcept override
00095 { return 0; }
00096
00098 int set_status_flags(long) noexcept override
00099 { return 0; }
00100
00102 int get_lock(struct flock64 *) noexcept override
00103 { return -ENOLCK; }
00104
00106 int set_lock(struct flock64 *, bool) noexcept override
00107 { return -ENOLCK; }
00108
00110 int faccessat(const char *, int, int) noexcept override
00111 { return -ENOTDIR; }
00112
00114 int fchmodat(const char *, mode_t, int) noexcept override
00115 { return -ENOTDIR; }
00116
00118 int utime(const struct utimbuf *) noexcept override
00119 { return -EROFS; }
00120
00122 int utimes(const struct timeval [2]) noexcept override
00123 { return -EROFS; }
00124
00126 int utimensat(const char *, const struct timespec [2], int) noexcept override
00127 { return -EROFS; }
00128
00130 int mkdir(const char *, mode_t) noexcept override
00131 { return -ENOTDIR; }
00132
00134 int unlink(const char *) noexcept override
00135 { return -ENOTDIR; }
00136
00138 int rename(const char *, const char *) noexcept override
00139 { return -ENOTDIR; }
00140
00142 int link(const char *, const char *) noexcept override
00143 { return -ENOTDIR; }
00144
00146 int symlink(const char *, const char *) noexcept override
00147 { return -EPERM; }
00148
00150 int rmdir(const char *) noexcept override
00151 { return -ENOTDIR; }
00152
00154 ssize_t readlink(char *, size_t) override
00155 { return -EINVAL; }
00156
00157 ssize_t getdents(char *, size_t) noexcept override
00158 { return -ENOTDIR; }
00159
00160
00161
00162 // Socket interface
00163 int bind(sockaddr const *, socklen_t) noexcept override
00164 { return -ENOTSOCK; }
00165
00166 int connect(sockaddr const *, socklen_t) noexcept override
00167 { return -ENOTSOCK; }
00168
00169 ssize_t send(void const *, size_t, int) noexcept override
00170 { return -ENOTSOCK; }
00171
00172 ssize_t recv(void *, size_t, int) noexcept override
00173 { return -ENOTSOCK; }
00174
00175 ssize_t sendto(void const *, size_t, int, sockaddr const *, socklen_t) noexcept
00176 override
00177 { return -ENOTSOCK; }

```

```

00178
00179 ssize_t recvfrom(void *, size_t, int, sockaddr *, socklen_t *) noexcept override
00180 { return -ENOTSOCK; }
00181
00182 ssize_t sendmsg(msghdr const *, int) noexcept override
00183 { return -ENOTSOCK; }
00184
00185 ssize_t recvmsg(msghdr *, int) noexcept override
00186 { return -ENOTSOCK; }
00187
00188 int getsockopt(int, int, void *, socklen_t *) noexcept override
00189 { return -ENOTSOCK; }
00190
00191 int setsockopt(int, int, void const *, socklen_t) noexcept override
00192 { return -ENOTSOCK; }
00193
00194 int listen(int) noexcept override
00195 { return -ENOTSOCK; }
00196
00197 int accept(sockaddr *, socklen_t *) noexcept override
00198 { return -ENOTSOCK; }
00199
00200 int shutdown(int) noexcept override
00201 { return -ENOTSOCK; }
00202
00203 int getsockname(sockaddr *, socklen_t *) noexcept override
00204 { return -ENOTSOCK; }
00205
00206 int getpeername(sockaddr *, socklen_t *) noexcept override
00207 { return -ENOTSOCK; }
00208
00217 bool check_ready(Ready_type) noexcept override
00218 { return false; }
00219
00220 ~Be_file() noexcept = 0;
00221
00222 private:
00224 int get_entry(const char *, int, mode_t, cxx::Ref_ptr<File> *) noexcept override
00225 { return -ENOTDIR; }
00226
00227 protected:
00228 const char *get_mount(const char *path, cxx::Ref_ptr<File> *dir) noexcept;
00229 };
00230
00231 inline
00232 Be_file::~Be_file() noexcept {}
00233
00234 class Be_file_pos : public Be_file
00235 {
00236 public:
00237 Be_file_pos() noexcept : Be_file(), _pos(0) {}
00238
00239 virtual off64_t size() const noexcept = 0;
00240
00241 ssize_t readv(const struct iovec *v, int iovcnt) noexcept override
00242 {
00243     ssize_t r = preadv(v, iovcnt, _pos);
00244     if (r > 0)
00245         _pos += r;
00246     return r;
00247 }
00248
00249 ssize_t writev(const struct iovec *v, int iovcnt) noexcept override
00250 {
00251     ssize_t r = pwritev(v, iovcnt, _pos);
00252     if (r > 0)
00253         _pos += r;
00254     return r;
00255 }
00256
00257 ssize_t preadv(const struct iovec *v, int iovcnt, off64_t offset) noexcept override = 0;
00258 ssize_t pwritev(const struct iovec *v, int iovcnt, off64_t offset) noexcept override = 0;
00259
00260 off64_t lseek(off64_t offset, int whence) noexcept override
00261 {
00262     off64_t r;
00263     switch (whence)
00264     {
00265     case SEEK_SET: r = offset; break;
00266     case SEEK_CUR: r = _pos + offset; break;
00267     case SEEK_END: r = size() + offset; break;
00268     default: return -EINVAL;
00269     };
00270
00271     if (r < 0)
00272         return -EINVAL;
00273

```

```

00274     _pos = r;
00275     return _pos;
00276 }
00277
00278 ~Be_file_pos() noexcept = 0;
00279
00280 protected:
00281     off64_t pos() const noexcept { return _pos; }
00282
00283 private:
00284     off64_t _pos;
00285 };
00286
00287 inline Be_file_pos::~Be_file_pos() noexcept {}
00288
00289 class Be_file_stream : public Be_file
00290 {
00291 public:
00292     ssize_t preadv(const struct iovec *v, int iovcnt, off64_t) noexcept override
00293     { return readv(v, iovcnt); }
00294
00295     ssize_t pwritev(const struct iovec *v, int iovcnt, off64_t) noexcept override
00296     { return writev(v, iovcnt); }
00297
00298     ~Be_file_stream() noexcept = 0;
00299 };
00300
00301 inline Be_file_stream::~Be_file_stream() noexcept {}
00302
00303 class Be_file_system : public File_system
00304 {
00305 private:
00306     char const *_fstype;
00307
00308 public:
00309     explicit Be_file_system(char const *fstype) noexcept
00310     : File_system(), _fstype(fstype)
00311     {
00312         vfs_ops->register_file_system(this);
00313     }
00314
00315     ~Be_file_system() noexcept
00316     {
00317         vfs_ops->unregister_file_system(this);
00318     }
00319
00320     char const *type() const noexcept override { return _fstype; }
00321 };
00322
00323 /* Make sure filesystems can register before the constructor of libmount
00324  * runs */
00325 #define L4RE_VFS_FILE_SYSTEM_ATTRIBUTE \
00326     __attribute__((init_priority(INIT_PRIO_LATE)))
00327
00328 }
00329
00330 }

```

## 16.245 default\_ops\_impl.h

```

00001 // vi:ft=cpp
00002 /*
00003  * Copyright (C) 2016, 2023-2024 Kernkonzept GmbH.
00004  * Author(s): Alexander Warg <alexander.warg@kernkonzept.com>
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00008 #include <l4/cxx/static_container>
00009
00010 namespace {
00011 struct Vfs_init
00012 {
00013     // The Static_containers are used to prevent automatic destruction during
00014     // program shutdown. At least the `vfs` object must never be destructed
00015     // because any later attempt to do any kind of file-descriptor access in
00016     // the program would crash, and we could not be sure that the destructor
00017     // would really be executed after each possible operation using files or file
00018     // descriptors.
00019     cxx::Static_container<Vfs> vfs;
00020
00021     // The Static_containers below are just for providing ordering. The factories
00022     // must be initialized after the `vfs` object.
00023     cxx::Static_container<L4Re::Vfs::File_factory_t<L4Re::Dataspace, L4Re::Core::Ro_file> > ro_file;

```

```

00024   cxx::Static_container<L4Re::Vfs::File_factory_t<L4Re::Namespace, L4Re::Core::Ns_dir> > ns_dir;
00025   cxx::Static_container<L4Re::Vfs::File_factory_t<L4::Vcon, L4Re::Core::Vcon_stream> > vcon_stream;
00026
00027   Vfs_init()
00028   {
00029       vfs.construct();
00030       __rtld_l4re_env_posix_vfs_ops = vfs;
00031       ns_dir.construct();
00032       auto ns_ptr = cxx::ref_ptr(ns_dir.get());
00033       vfs->register_file_factory(ns_ptr);
00034       ns_ptr.release(); // prevent deletion of static object
00035
00036       ro_file.construct();
00037       auto ro_ptr = cxx::ref_ptr(ro_file.get());
00038       vfs->register_file_factory(ro_ptr);
00039       ro_ptr.release(); // prevent deletion of static object
00040
00041       vcon_stream.construct();
00042       auto vcon_ptr = cxx::ref_ptr(vcon_stream.get());
00043       vfs->register_file_factory(vcon_ptr);
00044       vcon_ptr.release(); // prevent deletion of static object
00045   }
00046 };
00047
00048 static Vfs_init __vfs_init __attribute__((init_priority(INIT_PRIO_VFS_INIT)));
00049
00050 };

```

## 16.246 fd\_store.h

```

00001 /*
00002  * (c) 2010 Alexander Warg <warg@os.inf.tu-dresden.de>
00003  *     economic rights: Technische Universität Dresden (Germany)
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007 #pragma once
00008
00009 #include <l4/l4re_vfs/vfs.h>
00010
00011 namespace L4Re { namespace Core {
00012
00013     using cxx::Ref_ptr;
00014
00015     class Fd_store
00016     {
00017     public:
00018         enum { MAX_FILES = 50 };
00019
00020         Fd_store() noexcept : _fd_hint(0) {}
00021
00022         int alloc() noexcept;
00023         void free(int fd) noexcept;
00024         bool check_fd(int fd) noexcept;
00025         Ref_ptr<L4Re::Vfs::File> get(int fd) noexcept;
00026         void set(int fd, Ref_ptr<L4Re::Vfs::File> const &f) noexcept;
00027
00028     private:
00029         int _fd_hint;
00030         Ref_ptr<L4Re::Vfs::File> _files[MAX_FILES];
00031     };
00032
00033     inline
00034     bool
00035     Fd_store::check_fd(int fd) noexcept
00036     {
00037         return fd >= 0 && fd < MAX_FILES;
00038     }
00039
00040     inline
00041     Ref_ptr<L4Re::Vfs::File>
00042     Fd_store::get(int fd) noexcept
00043     {
00044         if (check_fd(fd))
00045             return _files[fd];
00046
00047         return Ref_ptr<>::Nil;
00048     }
00049
00050     inline
00051     void
00052     Fd_store::set(int fd, Ref_ptr<L4Re::Vfs::File> const &f) noexcept
00053     {

```



```

00054     _files[fd] = f;
00055 }
00056
00057 }}

```

## 16.247 fd\_store\_impl.h

```

00001 /*
00002  * (c) 2010 Alexander Warg <warg@os.inf.tu-dresden.de>
00003  *     economic rights: Technische Universität Dresden (Germany)
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007 #include "fd_store.h"
00008
00009 namespace L4Re { namespace Core {
00010
00011     int
00012     Fd_store::alloc() noexcept
00013     {
00014         for (int i = _fd_hint; i < MAX_FILES; ++i)
00015         {
00016             if (!_files[i])
00017             {
00018                 _fd_hint = i + 1;
00019                 return i;
00020             }
00021         }
00022
00023         return -1;
00024     }
00025
00026     void
00027     Fd_store::free(int fd) noexcept
00028     {
00029         _files[fd] = 0;
00030         if (fd < _fd_hint)
00031             _fd_hint = fd;
00032     }
00033
00034 }}
00035

```

## 16.248 ns\_fs.h

```

00001 /*
00002  * (c) 2010 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00003  *     Alexander Warg <warg@os.inf.tu-dresden.de>
00004  *     economic rights: Technische Universität Dresden (Germany)
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00008 #pragma once
00009
00010 #include <l4/l4re_vfs/backend>
00011 #include <l4/sys/capability>
00012 #include <l4/re/namespace>
00013 #include <l4/re/unique_cap>
00014
00015 namespace L4Re { namespace Core {
00016
00017     using cxx::Ref_ptr;
00018
00019     class Env_dir : public L4Re::Vfs::Be_file
00020     {
00021     public:
00022         explicit Env_dir(L4Re::Env const *env)
00023             : _env(env), _current_cap_entry(env->initial_caps())
00024         {}
00025
00026         ssize_t readv(const struct iovec*, int) noexcept override { return -EISDIR; }
00027         ssize_t writev(const struct iovec*, int) noexcept override { return -EISDIR; }
00028         ssize_t preadv(const struct iovec*, int, off64_t) noexcept override { return -EISDIR; }
00029         ssize_t pwritev(const struct iovec*, int, off64_t) noexcept override { return -EISDIR; }
00030         int fstat(struct stat64 *) const noexcept override;
00031         int faccessat(const char *path, int mode, int flags) noexcept override;
00032         int get_entry(const char *path, int flags, mode_t mode,
00033                     Ref_ptr<L4Re::Vfs::File> *) noexcept override;
00034

```

```

00034     ssize_t getdents(char *, size_t) noexcept override;
00035
00036     ~Env_dir() noexcept {}
00037
00038 private:
00039     int get_ds(const char *path, L4Re::Unique_cap<L4Re::Dataspace> *ds) noexcept;
00040     bool check_type(Env::Cap_entry const *e, long protocol) noexcept;
00041
00042     L4Re::Env const *_env;
00043     Env::Cap_entry const *_current_cap_entry;
00044 };
00045
00046 class Ns_dir : public L4Re::Vfs::Be_file
00047 {
00048 public:
00049     explicit Ns_dir(L4::Cap<L4Re::Namespace> ns)
00050         : _ns(ns), _current_dir_pos(0)
00051     {}
00052
00053     ssize_t readv(const struct iovec*, int) noexcept override { return -EISDIR; }
00054     ssize_t writev(const struct iovec*, int) noexcept override { return -EISDIR; }
00055     ssize_t preadv(const struct iovec*, int, off64_t) noexcept override { return -EISDIR; }
00056     ssize_t pwritev(const struct iovec*, int, off64_t) noexcept override { return -EISDIR; }
00057     int fstat(struct stat64 *) const noexcept override;
00058     int faccessat(const char *path, int mode, int flags) noexcept override;
00059     int get_entry(const char *path, int flags, mode_t mode,
00060                  Ref_ptr<L4Re::Vfs::File> *) noexcept override;
00061     ssize_t getdents(char *, size_t) noexcept override;
00062
00063     ~Ns_dir() noexcept {}
00064
00065 private:
00066     int get_ds(const char *path, L4Re::Unique_cap<L4Re::Dataspace> *ds) noexcept;
00067
00068     L4::Cap<L4Re::Namespace> _ns;
00069     size_t _current_dir_pos;
00070 };
00071
00072 {}

```

## 16.249 ns\_fs\_impl.h

```

00001 /*
00002  * (c) 2010 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00003  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00004  *      economic rights: Technische Universität Dresden (Germany)
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00008 #include "ns_fs.h"
00009
00010 #include <l4/re/dataspace>
00011 #include <l4/re/util/env_ns>
00012 #include <l4/re/unique_cap>
00013 #include <dirent.h>
00014
00015 namespace L4Re { namespace Core {
00016
00017     static
00018     Ref_ptr<L4Re::Vfs::File>
00019     cap_to_vfs_object(L4::Cap<void> o, int *err)
00020     {
00021         L4::Cap<L4::Meta> m = L4::cap_reinterpret_cast<L4::Meta>(o);
00022         long proto = 0;
00023         char name_buf[256];
00024         L4::Ipc::String<char> name(sizeof(name_buf), name_buf);
00025         l4_ret_t r = l4_error(m->interface(0, &proto, &name));
00026         *err = -ENOPROTOPT;
00027         if (r < 0)
00028             // could not get type of object so bail out
00029             return Ref_ptr<L4Re::Vfs::File>();
00030
00031         *err = -EPROTO;
00032         Ref_ptr<L4Re::Vfs::File_factory> factory;
00033
00034         if (proto != 0)
00035             factory = L4Re::Vfs::vfs_ops->get_file_factory(proto);
00036
00037         if (!factory)
00038             factory = L4Re::Vfs::vfs_ops->get_file_factory(name.data);
00039
00040         if (!factory)
00041             return Ref_ptr<L4Re::Vfs::File>();

```

```

00042
00043     *err = -ENOMEM;
00044     return factory->create(o);
00045 }
00046
00047
00048 int
00049 Ns_dir::get_ds(const char *path, L4Re::Unique_cap<L4Re::Dataspace> *ds) noexcept
00050 {
00051     auto file = L4Re::make_unique_cap<L4Re::Dataspace>(L4Re::virt_cap_alloc);
00052
00053     if (!file.is_valid())
00054         return -ENOMEM;
00055
00056     int err = _ns->query(path, file.get());
00057
00058     if (err < 0)
00059         return -ENOENT;
00060
00061     *ds = cxx::move(file);
00062     return err;
00063 }
00064
00065 int
00066 Ns_dir::get_entry(const char *path, int /*flags*/, mode_t /*mode*/,
00067                  Ref_ptr<L4Re::Vfs::File> *f) noexcept
00068 {
00069     if (!*path)
00070     {
00071         *f = cxx::ref_ptr(this);
00072         return 0;
00073     }
00074
00075     L4Re::Unique_cap<Dataspace> file;
00076     int err = get_ds(path, &file);
00077
00078     if (err < 0)
00079         return -ENOENT;
00080
00081     cxx::Ref_ptr<L4Re::Vfs::File> fi = cap_to_vfs_object(file.get(), &err);
00082     if (!fi)
00083         return err;
00084
00085     file.release();
00086     *f = cxx::move(fi);
00087     return 0;
00088 }
00089
00090 int
00091 Ns_dir::faccessat(const char *path, int mode, int /*flags*/) noexcept
00092 {
00093     auto tmpcap = L4Re::make_unique_cap<void>(L4Re::virt_cap_alloc);
00094
00095     if (!tmpcap.is_valid())
00096         return -ENOMEM;
00097
00098     if (_ns->query(path, tmpcap.get()))
00099         return -ENOENT;
00100
00101     if (mode & W_OK)
00102         return -EACCES;
00103
00104     return 0;
00105 }
00106
00107 int
00108 Ns_dir::fstat(struct stat64 *b) const noexcept
00109 {
00110     b->st_dev = 1;
00111     b->st_ino = 1;
00112     b->st_mode = S_IRWXU | S_IFDIR;
00113     b->st_nlink = 0;
00114     b->st_uid = 0;
00115     b->st_gid = 0;
00116     b->st_rdev = 0;
00117     b->st_size = 0;
00118     b->st_blksize = 0;
00119     b->st_blocks = 0;
00120     b->st_atime = 0;
00121     b->st_mtime = 0;
00122     b->st_ctime = 0;
00123     return 0;
00124 }
00125
00126 ssize_t
00127 Ns_dir::getdents(char *buf, size_t dest_sz) noexcept
00128 {

```

```

00129 struct dirent64 *dest = reinterpret_cast<struct dirent64 *>(buf);
00130 ssize_t ret = 0;
00131 L4_addr_t infoaddr;
00132 size_t infosz;
00133
00134 L4Re::Unique_cap<Dataspace> dirinfofile;
00135 int err = get_ds(".dirinfo", &dirinfofile);
00136 if (err)
00137     return 0;
00138
00139 infosz = dirinfofile->size();
00140 if (infosz <= 0)
00141     return 0;
00142
00143 infoaddr = L4_PAGESIZE;
00144 err = L4Re::Env::env()->rm()->attach(&infoaddr, infosz,
00145                                     Rm::F::Search_addr | Rm::F::R,
00146                                     dirinfofile.get(), 0);
00147 if (err < 0)
00148     return 0;
00149
00150 char *p = reinterpret_cast<char *>(infoaddr) + _current_dir_pos;
00151 char *end = reinterpret_cast<char *>(infoaddr) + infosz;
00152
00153 char *current_dirinfo_entry = p;
00154 while (dest && p < end)
00155 {
00156     // parse lines of dirinfofile
00157     long len = 0;
00158     for (; p < end && *p >= '0' && *p <= '9'; ++p)
00159     {
00160         len *= 10;
00161         len += *p - '0';
00162     }
00163
00164     if (len == 0)
00165         break;
00166
00167     if (p == end)
00168         break;
00169
00170     if (*p != ':')
00171         break;
00172     p++; // skip colon
00173
00174     if (p + len >= end)
00175         break;
00176
00177     unsigned l = len + 1;
00178     if (l > sizeof(dest->d_name))
00179         l = sizeof(dest->d_name);
00180
00181     unsigned n = offsetof(struct dirent64, d_name) + 1;
00182     n = (n + sizeof(long) - 1) & ~(sizeof(long) - 1);
00183
00184     if (n > dest_sz)
00185         break;
00186
00187     dest->d_ino = 1;
00188     dest->d_off = 0;
00189     memcpy(dest->d_name, p, l - 1);
00190     dest->d_name[l - 1] = 0;
00191     dest->d_reclen = n;
00192     dest->d_type = DT_UNKNOWN;
00193     ret += n;
00194     dest_sz -= n;
00195
00196     // next entry
00197     dest = reinterpret_cast<struct dirent64 *>
00198           (reinterpret_cast<unsigned long>(dest) + n);
00199
00200     // next infodirfile line
00201     p += len;
00202     while (p < end && *p && (*p == '\\n' || *p == '\\r'))
00203         p++;
00204
00205     current_dirinfo_entry = p;
00206 }
00207
00208 _current_dir_pos = current_dirinfo_entry - reinterpret_cast<char *>(infoaddr);
00209
00210 if (!ret) // hack since we should only reset this at open times
00211     _current_dir_pos = 0;
00212
00213 L4Re::Env::env()->rm()->detach(infoaddr, 0);
00214
00215 return ret;

```

```

00216 }
00217
00218 int
00219 Env_dir::get_ds(const char *path, L4Re::Unique_cap<L4Re::Dataspace> *ds) noexcept
00220 {
00221     while (*path == '/')
00222         ++path;
00223     Vfs::Path p(path);
00224     Vfs::Path first = p.strip_first();
00225
00226     if (first.empty())
00227         return -ENOENT;
00228
00229     L4::Cap<L4Re::Namespace>
00230     c = _env->get_cap<L4Re::Namespace>(first.path(), first.length());
00231
00232     if (!c.is_valid())
00233         return -ENOENT;
00234
00235     if (p.empty())
00236     {
00237         *ds = L4Re::Unique_cap<L4Re::Dataspace>(L4::cap_reinterpret_cast<L4Re::Dataspace>(c));
00238         return 0;
00239     }
00240
00241     auto file = L4Re::make_unique_cap<L4Re::Dataspace>(L4Re::virt_cap_alloc);
00242
00243     if (!file.is_valid())
00244         return -ENOMEM;
00245
00246     int err = c->query(p.path(), p.length(), file.get());
00247
00248     if (err < 0)
00249         return -ENOENT;
00250
00251     *ds = cxx::move(file);
00252     return err;
00253 }
00254
00255 int
00256 Env_dir::get_entry(const char *path, int /*flags*/, mode_t /*mode*/,
00257                   Ref_ptr<L4Re::Vfs::File> *f) noexcept
00258 {
00259     if (!*path)
00260     {
00261         *f = cxx::ref_ptr(this);
00262         return 0;
00263     }
00264
00265     L4Re::Unique_cap<Dataspace> file;
00266     int err = get_ds(path, &file);
00267
00268     if (err < 0)
00269         return -ENOENT;
00270
00271     cxx::Ref_ptr<L4Re::Vfs::File> fi = cap_to_vfs_object(file.get(), &err);
00272     if (!fi)
00273         return err;
00274
00275     file.release();
00276     *f = cxx::move(fi);
00277     return 0;
00278 }
00279
00280 int
00281 Env_dir::faccessat(const char *path, int mode, int /*flags*/) noexcept
00282 {
00283     while (*path == '/')
00284         ++path;
00285     Vfs::Path p(path);
00286     Vfs::Path first = p.strip_first();
00287
00288     if (first.empty())
00289         return -ENOENT;
00290
00291     L4::Cap<L4Re::Namespace>
00292     c = _env->get_cap<L4Re::Namespace>(first.path(), first.length());
00293
00294     if (!c.is_valid())
00295         return -ENOENT;
00296
00297     if (p.empty())
00298     {
00299         if (mode & W_OK)
00300             return -EACCES;
00301
00302         return 0;

```

```

00303     }
00304
00305     auto tmpcap = L4Re::make_unique_cap<void>(L4Re::virt_cap_alloc);
00306
00307     if (!tmpcap.is_valid())
00308         return -ENOMEM;
00309
00310     if (c->query(p.path(), p.length(), tmpcap.get()))
00311         return -ENOENT;
00312
00313     if (mode & W_OK)
00314         return -EACCES;
00315
00316     return 0;
00317 }
00318
00319 bool
00320 Env_dir::check_type(Env::Cap_entry const *e, long protocol) noexcept
00321 {
00322     L4::Cap<L4::Meta> m(e->cap);
00323     return m->supports(protocol).label();
00324 }
00325
00326 int
00327 Env_dir::fstat(struct stat64 *b) const noexcept
00328 {
00329     b->st_dev = 1;
00330     b->st_ino = 1;
00331     b->st_mode = S_IRWXU | S_IFDIR;
00332     b->st_nlink = 0;
00333     b->st_uid = 0;
00334     b->st_gid = 0;
00335     b->st_rdev = 0;
00336     b->st_size = 0;
00337     b->st_blksize = 0;
00338     b->st_blocks = 0;
00339     b->st_atime = 0;
00340     b->st_mtime = 0;
00341     b->st_ctime = 0;
00342     return 0;
00343 }
00344
00345 ssize_t
00346 Env_dir::getdents(char *buf, size_t sz) noexcept
00347 {
00348     struct dirent64 *d = reinterpret_cast<struct dirent64 *>(buf);
00349     ssize_t ret = 0;
00350
00351     while (d
00352            && _current_cap_entry
00353            && _current_cap_entry->flags != ~0UL)
00354     {
00355         unsigned l = strlen(_current_cap_entry->name) + 1;
00356         if (l > sizeof(d->d_name))
00357             l = sizeof(d->d_name);
00358
00359         unsigned n = offsetof(struct dirent64, d_name) + 1;
00360         n = (n + sizeof(long) - 1) & ~(sizeof(long) - 1);
00361
00362         if (n <= sz)
00363         {
00364             d->d_ino = 1;
00365             d->d_off = 0;
00366             memcpy(d->d_name, _current_cap_entry->name, l);
00367             d->d_name[l - 1] = 0;
00368             d->d_reclen = n;
00369             if (check_type(_current_cap_entry, L4Re::Namespace::Protocol))
00370                 d->d_type = DT_DIR;
00371             else if (check_type(_current_cap_entry, L4Re::Dataspace::Protocol))
00372                 d->d_type = DT_REG;
00373             else
00374                 d->d_type = DT_UNKNOWN;
00375             ret += n;
00376             sz -= n;
00377             d = reinterpret_cast<struct dirent64 *>
00378                 (reinterpret_cast<unsigned long*>(d) + n);
00379             _current_cap_entry++;
00380         }
00381         else
00382             return ret;
00383     }
00384
00385     // bit of a hack because we should only (re)set this when opening the dir
00386     if (!ret)
00387         _current_cap_entry = _env->initial_caps();
00388
00389     return ret;

```

```
00390 }
00391
00392 }}
```

## 16.250 ro\_file.h

```
00001 /*
00002  * (c) 2010 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00003  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00004  *      economic rights: Technische Universität Dresden (Germany)
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00008 #pragma once
00009
00010 #include <l4/l4re_vfs/backend>
00011
00012 namespace L4Re { namespace Core {
00013
00014 class Ro_file : public L4Re::Vfs::Be_file_pos
00015 {
00016 private:
00017     L4::Cap<L4Re::Dataspace> _ds;
00018     off64_t _size;
00019     char const *_addr;
00020
00021 public:
00022     explicit Ro_file(L4::Cap<L4Re::Dataspace> ds) noexcept
00023         : Be_file_pos(), _ds(ds), _addr(0)
00024     {
00025         _size = _ds->size();
00026     }
00027
00028     L4::Cap<L4Re::Dataspace> data_space() noexcept override { return _ds; }
00029
00030     int fstat(struct stat64 *buf) const noexcept override;
00031
00032     int ioctl(unsigned long, va_list) noexcept override;
00033
00034     off64_t size() const noexcept override { return _size; }
00035
00036     int get_status_flags() const noexcept override
00037     { return O_RDONLY; }
00038
00039     int set_status_flags(long) noexcept override
00040     { return 0; }
00041
00052     bool check_ready(Ready_type rt) noexcept override
00053     { return rt == Read; }
00054
00055     ~Ro_file() noexcept;
00056
00057 private:
00058     ssize_t read_single(const struct iovec*, off64_t) noexcept;
00059     ssize_t preadv(const struct iovec *, int, off64_t) noexcept override;
00060     ssize_t pwritev(const struct iovec *, int , off64_t) noexcept override;
00061 };
00062
00063
00064 }}
```

## 16.251 ro\_file\_impl.h

```
00001 /*
00002  * (c) 2010 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00003  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00004  *      economic rights: Technische Universität Dresden (Germany)
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00008
00009 #include "ro_file.h"
00010
00011 #include <sys/ioctl.h>
00012
00013 #include <l4/re/env>
00014
00015 namespace L4Re { namespace Core {
```

```

00016
00017 Ro_file::~~Ro_file() noexcept
00018 {
00019     if (_addr)
00020         L4Re::Env::env()->rm()->detach(l4_addr_t(_addr), 0);
00021
00022     L4Re::virt_cap_alloc->release(_ds);
00023 }
00024
00025 int
00026 Ro_file::fstat(struct stat64 *buf) const noexcept
00027 {
00028     static int fake = 0;
00029
00030     memset(buf, 0, sizeof(*buf));
00031     buf->st_size = _size;
00032     buf->st_mode = S_IFREG | 0644;
00033     buf->st_dev = _ds.cap();
00034     buf->st_ino = ++fake;
00035     buf->st_blksize = L4_PAGE_SIZE;
00036     buf->st_blocks = l4_round_page(_size);
00037     return 0;
00038 }
00039
00040 ssize_t
00041 Ro_file::read_single(const struct iovec *vec, off64_t pos) noexcept
00042 {
00043     off64_t l = vec->iiov_len;
00044     if (_size - pos < l)
00045         l = _size - pos;
00046
00047     if (l > 0)
00048     {
00049         Vfs_config::memcpy(vec->iiov_base, _addr + pos, l);
00050         return l;
00051     }
00052
00053     return 0;
00054 }
00055
00056 ssize_t
00057 Ro_file::preadv(const struct iovec *vec, int cnt, off64_t offset) noexcept
00058 {
00059     if (!_addr)
00060     {
00061         void const *file = reinterpret_cast<void*>(L4_PAGE_SIZE);
00062         long err = L4Re::Env::env()->rm()->attach(&file, _size,
00063             Rm::F::Search_addr | Rm::F::R,
00064             _ds, 0);
00065
00066         if (err < 0)
00067             return err;
00068
00069         _addr = static_cast<char const *>(file);
00070     }
00071
00072     ssize_t l = 0;
00073
00074     while (cnt > 0)
00075     {
00076         ssize_t r = read_single(vec, offset);
00077         offset += r;
00078         l += r;
00079
00080         if (static_cast<size_t>(r) < vec->iiov_len)
00081             return l;
00082
00083         ++vec;
00084         --cnt;
00085     }
00086     return l;
00087 }
00088
00089 ssize_t
00090 Ro_file::pwritev(const struct iovec *, int, off64_t) noexcept
00091 {
00092     return -EROFS;
00093 }
00094
00095 int
00096 Ro_file::ioctl(unsigned long v, va_list args) noexcept
00097 {
00098     switch (v)
00099     {
00100         case FIONREAD: // return amount of data still available
00101             int *available = va_arg(args, int *);
00102             *available = _size - pos();

```



```

00103         return 0;
00104     };
00105     return -ENOTTY;
00106 }
00107
00108 }}

```

## 16.252 vcon\_stream.h

```

00001 /*
00002  * (c) 2010 Alexander Warg <warg@os.inf.tu-dresden.de>
00003  *     economic rights: Technische Universität Dresden (Germany)
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007 #pragma once
00008
00009 #include <l4/sys/capability>
00010 #include <l4/sys/vcon>
00011 #include <l4/sys/semaphore>
00012
00013 #include <l4/l4re_vfs/backend>
00014
00015 namespace L4Re { namespace Core {
00016
00017     class Vcon_stream : public L4Re::Vfs::Be_file_stream
00018     {
00019     private:
00020         L4::Cap<L4::Vcon> _s;
00021         L4::Cap<L4::Semaphore> _irq;
00022         unsigned _irq_bound;
00023
00024     public:
00025         explicit Vcon_stream(L4::Cap<L4::Vcon> s) noexcept;
00026
00027         ssize_t readv(const struct iovec*, int iovcnt) noexcept override;
00028         ssize_t writev(const struct iovec*, int iovcnt) noexcept override;
00029         int fstat(struct stat64 *buf) const noexcept override;
00030         int get_status_flags() const noexcept override { return O_RDWR; }
00031         int set_status_flags(long) noexcept override { return 0; }
00032         int ioctl(unsigned long request, va_list args) noexcept override;
00033
00034         ~Vcon_stream() noexcept {}
00035         void operator delete (void *) {}
00036     };
00037
00038 }}

```

## 16.253 vcon\_stream\_impl.h

```

00001 /*
00002  * (c) 2010 Alexander Warg <warg@os.inf.tu-dresden.de>
00003  *     economic rights: Technische Universität Dresden (Germany)
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007
00008 #include <l4/re/env>
00009 #include <l4/sys/factory>
00010 #include <l4/cxx/minmax>
00011
00012 #include "vcon_stream.h"
00013
00014 #include <limits.h>
00015 #include <termios.h>
00016 #include <unistd.h>
00017 #include <sys/ioctl.h>
00018 #include <sys/ttydefaults.h>
00019
00020 namespace L4Re { namespace Core {
00021     Vcon_stream::Vcon_stream(L4::Cap<L4::Vcon> s) noexcept
00022     : Be_file_stream(),
00023       _s(s), _irq(L4Re::virt_cap_alloc->alloc<L4::Semaphore>()), _irq_bound(false)
00024     {
00025         // [[maybe_unused]] int res =
00026         l4_error(L4Re::Env::env()->factory()->create(_irq));
00027         // (void)res; // handle errors!
00028     }

```

```

00029
00030 ssize_t
00031 Vcon_stream::readv(const struct iovec *iovec, int iovcnt) noexcept
00032 {
00033     if (iovcnt < 0)
00034         return -EINVAL;
00035
00036     if (!_irq_bound)
00037     {
00038         bool was_bound = __atomic_exchange_n(&_irq_bound, true, __ATOMIC_SEQ_CST);
00039         if (!was_bound)
00040             if (l4_error(_s->bind(0, _irq)) < 0)
00041                 return -EIO;
00042     }
00043
00044     ssize_t bytes = 0;
00045     for (; iovcnt > 0; --iovcnt, ++iovec)
00046     {
00047         size_t len = cxx::min<size_t>(iovec->iov_len, SSIZE_MAX - bytes);
00048         if (len == 0)
00049             continue;
00050
00051         char *buf = static_cast<char *>(iovec->iov_base);
00052
00053         while (1)
00054         {
00055             size_t l = cxx::min<size_t>(L4_VCON_READ_SIZE, len);
00056             int ret = _s->read(buf, l);
00057
00058             if (ret > static_cast<int>(l))
00059                 ret = l;
00060
00061             if (ret < 0)
00062                 return ret;
00063             else if (ret == 0)
00064             {
00065                 if (bytes)
00066                     return bytes;
00067
00068                 ret = _s->read(buf, l);
00069                 if (ret < 0)
00070                     return ret;
00071                 else if (ret == 0)
00072                 {
00073                     _irq->down();
00074                     continue;
00075                 }
00076             }
00077
00078             bytes += ret;
00079             len -= ret;
00080             buf += ret;
00081
00082             if (len == 0)
00083                 break;
00084         }
00085     }
00086
00087     return bytes;
00088 }
00089
00090 ssize_t
00091 Vcon_stream::writev(const struct iovec *iovec, int iovcnt) noexcept
00092 {
00093     l4_msg_regs_t store;
00094     l4_msg_regs_t *mr = l4_utcb_mr();
00095
00096     if (iovcnt < 0)
00097         return -EINVAL;
00098
00099     Vfs_config::memcpy(&store, mr, sizeof(store));
00100
00101     ssize_t written = 0;
00102     while (iovcnt)
00103     {
00104         size_t sl = cxx::min<size_t>(iovec->iov_len, SSIZE_MAX - written);
00105         char const *b = static_cast<char const *>(iovec->iov_base);
00106
00107         for (; sl > L4_VCON_WRITE_SIZE;
00108             ; sl -= L4_VCON_WRITE_SIZE, b += L4_VCON_WRITE_SIZE,
00109             written += L4_VCON_WRITE_SIZE)
00110             _s->send(b, L4_VCON_WRITE_SIZE);
00111
00112         _s->send(b, sl);
00113
00114         written += sl;
00115     }

```

```

00116         ++iovec;
00117         --iocvnt;
00118     }
00119     Vfs_config::memcpy(mr, &store, sizeof(store));
00120     return written;
00121 }
00122
00123 int
00124 Vcon_stream::fstat(struct stat64 *buf) const noexcept
00125 {
00126     buf->st_size = 0;
00127     buf->st_mode = 0666;
00128     buf->st_dev = _s.cap();
00129     buf->st_ino = 0;
00130     return 0;
00131 }
00132
00133 int
00134 Vcon_stream::ioctl(unsigned long request, va_list args) noexcept
00135 {
00136     switch (request) {
00137     case TCGETS:
00138     {
00139         //vt100_tcgetattr(term, (struct termios *)argp);
00140
00141         struct termios *t = va_arg(args, struct termios *);
00142
00143         l4_vcon_attr_t l4a;
00144         if (!l4_error(_s->get_attr(&l4a)))
00145         {
00146             t->c_iflag = l4a.i_flags;
00147             t->c_oflag = l4a.o_flags; // output flags
00148             t->c_cflag = 0; // control flags
00149             t->c_lflag = l4a.l_flags; // local flags
00150         }
00151         else
00152             t->c_iflag = t->c_oflag = t->c_cflag = t->c_lflag = 0;
00153         #if 0
00154             //t->c_lflag |= ECHO; // if term->echo
00155             t->c_lflag |= ICANON; // if term->term_mode == VT100MODE_COOKED
00156         #endif
00157
00158         t->c_cc[VEOF] = CEOF;
00159         t->c_cc[VEOL] = _POSIX_VDISABLE;
00160         t->c_cc[VEOL2] = _POSIX_VDISABLE;
00161         t->c_cc[VERASE] = CERASE;
00162         t->c_cc[VWERASE] = CWERASE;
00163         t->c_cc[VKILL] = CKILL;
00164         t->c_cc[VREPRINT] = CREPRINT;
00165         t->c_cc[VINTR] = CINTR;
00166         t->c_cc[VQUIT] = _POSIX_VDISABLE;
00167         t->c_cc[VSUSP] = CSUSP;
00168         t->c_cc[VSTART] = CSTART;
00169         t->c_cc[VSTOP] = CSTOP;
00170         t->c_cc[VLNEXT] = CLNEXT;
00171         t->c_cc[VDISCARD] = CDISCARD;
00172         t->c_cc[VMIN] = CMIN;
00173         t->c_cc[VTIME] = 0;
00174     }
00175
00176     return 0;
00177
00178     case TCSETS:
00179     case TCSETSW:
00180     case TCSETSF:
00181     {
00182         //vt100_tcsetattr(term, (struct termios *)argp);
00183         struct termios const *t = va_arg(args, struct termios const *);
00184
00185         // XXX: well, we're cheating, get this from the other side!
00186
00187         l4_vcon_attr_t l4a;
00188         l4a.i_flags = t->c_iflag;
00189         l4a.o_flags = t->c_oflag; // output flags
00190         l4a.l_flags = t->c_lflag; // local flags
00191         _s->set_attr(&l4a);
00192     }
00193     return 0;
00194
00195     default:
00196         break;
00197     };
00198     return -ENOTTY;
00199 }
00200 }
00201
00202 }

```

## 16.254 vfs\_impl.h

```

00001 /*
00002  * (c) 2008-2010 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00003  *           Alexander Warg <warg@os.inf.tu-dresden.de>,
00004  *           Björn Döbel <doebel@os.inf.tu-dresden.de>
00005  *           economic rights: Technische Universität Dresden (Germany)
00006  *
00007  * License: see LICENSE.spdx (in this directory or the directories above)
00008  */
00009
00010 #include "fd_store.h"
00011 #include "vcon_stream.h"
00012 #include "ns_fs.h"
00013
00014 #include <l4/bid_config.h>
00015 #include <l4/re/env>
00016 #include <l4/re/rm>
00017 #include <l4/re/dataspace>
00018 #include <l4/sys/assert.h>
00019 #include <l4/cxx/hlist>
00020 #include <l4/cxx/pair>
00021 #include <l4/cxx/std_alloc>
00022
00023 #include <l4/l4re_vfs/backend>
00024 #include <l4/re/shared_cap>
00025
00026 #include <unistd.h>
00027 #include <stdarg.h>
00028 #include <errno.h>
00029 #include <sys/uio.h>
00030 #include <sys/mman.h>
00031
00032 #if 0
00033 #include <l4/sys/kdebug.h>
00034 static int debug_mmap = 1;
00035 #define DEBUG_LOG(level, dbg...) do { if (level) dbg } while (0)
00036 #else
00037 #define DEBUG_LOG(level, dbg...) do { } while (0)
00038 #endif
00039
00040 #define USE_BIG_ANON_DS
00041
00042 using L4Re::Rm;
00043
00044 namespace {
00045 using cxx::Ref_ptr;
00046
00047 class Fd_store : public L4Re::Core::Fd_store
00048 {
00049 public:
00050     Fd_store() noexcept;
00051 };
00052
00053 // for internal Vcon_streams we want to have a placement new operator, so
00054 // inherit and add one
00055 class Std_stream : public L4Re::Core::Vcon_stream
00056 {
00057 public:
00058     Std_stream(L4::Cap<L4::Vcon> c) : L4Re::Core::Vcon_stream(c) {}
00059 };
00060
00061 Fd_store::Fd_store() noexcept
00062 {
00063     // use this strange way to prevent deletion of the stdio object
00064     // this depends on Fd_store to being a singleton !!!
00065     static char m[sizeof(Std_stream)] __attribute__((aligned(sizeof(long))));
00066     if (auto log = L4Re::Env::env()->log())
00067     {
00068         Std_stream *s = new (m) Std_stream(log);
00069         set(0, cxx::ref_ptr(s)); // stdin
00070         set(1, cxx::ref_ptr(s)); // stdout
00071         set(2, cxx::ref_ptr(s)); // stderr
00072
00073         // make sure that we never delete the static io stream thing
00074         s->add_ref();
00075     }
00076 }
00077
00078 class Root_mount_tree : public L4Re::Vfs::Mount_tree
00079 {
00080 public:
00081     Root_mount_tree() : L4Re::Vfs::Mount_tree(0) {}
00082     void operator delete (void *) {}
00083 };

```

```

00090
00091 class Vfs : public L4Re::Vfs::Ops
00092 {
00093 private:
00094     bool _early_oom;
00095
00096 public:
00097     Vfs()
00098     : _early_oom(true), _root_mount(), _root(L4Re::Env::env())
00099     {
00100         _root_mount.add_ref();
00101         _root.add_ref();
00102         _root_mount.mount(cxx::ref_ptr(&_root));
00103         _cwd = cxx::ref_ptr(&_root);
00104
00105 #if 0
00106         Ref_ptr<L4Re::Vfs::File> rom;
00107         _root.openat("rom", 0, 0, &rom);
00108
00109         _root_mount.create_tree("lib/foo", rom);
00110
00111         _root.openat("lib", 0, 0, &_cwd);
00112
00113 #endif
00114     }
00115
00116     int alloc_fd(Ref_ptr<L4Re::Vfs::File> const &f) noexcept override;
00117     Ref_ptr<L4Re::Vfs::File> free_fd(int fd) noexcept override;
00118     Ref_ptr<L4Re::Vfs::File> get_root() noexcept override;
00119     Ref_ptr<L4Re::Vfs::File> get_cwd() noexcept override;
00120     void set_cwd(Ref_ptr<L4Re::Vfs::File> const &dir) noexcept override;
00121     Ref_ptr<L4Re::Vfs::File> get_file(int fd) noexcept override;
00122     cxx::Pair<Ref_ptr<L4Re::Vfs::File>, int>
00123         set_fd(int fd, Ref_ptr<L4Re::Vfs::File> const &f = Ref_ptr<>::Nil) noexcept
00124         override;
00125
00126     int mmap2(void *start, size_t len, int prot, int flags, int fd,
00127               off_t offset, void **ptr) noexcept override;
00128
00129     int munmap(void *start, size_t len) noexcept override;
00130     int mremap(void *old, size_t old_sz, size_t new_sz, int flags,
00131                void **new_addr) noexcept override;
00132     int mprotect(const void *a, size_t sz, int prot) noexcept override;
00133     int msync(void *addr, size_t len, int flags) noexcept override;
00134     int madvise(void *addr, size_t len, int advice) noexcept override;
00135
00136     int register_file_system(L4Re::Vfs::File_system *f) noexcept override;
00137     int unregister_file_system(L4Re::Vfs::File_system *f) noexcept override;
00138     L4Re::Vfs::File_system *get_file_system(char const *fstype) noexcept override;
00139     L4Re::Vfs::File_system_list file_system_list() noexcept override;
00140
00141     int register_file_factory(cxx::Ref_ptr<L4Re::Vfs::File_factory> f) noexcept override;
00142     int unregister_file_factory(cxx::Ref_ptr<L4Re::Vfs::File_factory> f) noexcept override;
00143     Ref_ptr<L4Re::Vfs::File_factory> get_file_factory(int proto) noexcept override;
00144     Ref_ptr<L4Re::Vfs::File_factory> get_file_factory(char const *proto_name) noexcept override;
00145     int mount(char const *path, cxx::Ref_ptr<L4Re::Vfs::File> const &dir) noexcept override;
00146
00147     void operator delete (void *) {}
00148
00149     void *malloc(size_t size) noexcept override { return Vfs_config::malloc(size); }
00150     void free(void *m) noexcept override { Vfs_config::free(m); }
00151
00152 private:
00153     Root_mount_tree _root_mount;
00154     L4Re::Core::Env_dir _root;
00155     Ref_ptr<L4Re::Vfs::File> _cwd;
00156     Fd_store fds;
00157
00158     L4Re::Vfs::File_system *_fs_registry;
00159
00160     struct File_factory_item : cxx::H_list_item_t<File_factory_item>
00161     {
00162         cxx::Ref_ptr<L4Re::Vfs::File_factory> f;
00163         explicit File_factory_item(cxx::Ref_ptr<L4Re::Vfs::File_factory> const &f)
00164             : f(f) {}
00165
00166         File_factory_item() = default;
00167         File_factory_item(File_factory_item const &) = delete;
00168         File_factory_item &operator = (File_factory_item const &) = delete;
00169     };
00170
00171     cxx::H_list_t<File_factory_item> _file_factories;
00172
00173     l4_addr_t _anon_offset;
00174     L4Re::Shared_cap<L4Re::Dataspace> _anon_ds;
00175
00176     int alloc_ds(unsigned long size, L4Re::Shared_cap<L4Re::Dataspace> *ds);

```

```

00177 int alloc_anon_mem(l4_umword_t size, L4Re::Shared_cap<L4Re::Dataspace> *ds,
00178                  l4_addr_t *offset);
00179
00180 void align_mmap_start_and_length(void **start, size_t *length);
00181 int munmap_regions(void *start, size_t len);
00182
00183 L4Re::Vfs::File_system *find_fs_from_type(char const *fstype) noexcept;
00184 };
00185
00186 static inline bool strequal(char const *a, char const *b)
00187 {
00188     for (; *a && *a == *b; ++a, ++b)
00189         ;
00190     return *a == *b;
00191 }
00192
00193 int
00194 Vfs::register_file_system(L4Re::Vfs::File_system *f) noexcept
00195 {
00196     using L4Re::Vfs::File_system;
00197
00198     if (!f)
00199         return -EINVAL;
00200
00201     for (File_system *c = _fs_registry; c; c = c->next())
00202         if (strequal(c->type(), f->type()))
00203             return -EEXIST;
00204
00205     f->next(_fs_registry);
00206     _fs_registry = f;
00207
00208     return 0;
00209 }
00210
00211 int
00212 Vfs::unregister_file_system(L4Re::Vfs::File_system *f) noexcept
00213 {
00214     using L4Re::Vfs::File_system;
00215
00216     if (!f)
00217         return -EINVAL;
00218
00219     File_system **p = &_fs_registry;
00220
00221     for (; *p; p = &(*p)->next())
00222         if (*p == f)
00223         {
00224             *p = f->next();
00225             f->next() = 0;
00226             return 0;
00227         }
00228
00229     return -ENOENT;
00230 }
00231
00232 L4Re::Vfs::File_system *
00233 Vfs::find_fs_from_type(char const *fstype) noexcept
00234 {
00235     L4Re::Vfs::File_system_list fsl(_fs_registry);
00236     for (L4Re::Vfs::File_system_list::Iterator c = fsl.begin();
00237          c != fsl.end(); ++c)
00238         if (strequal(c->type(), fstype))
00239             return *c;
00240     return 0;
00241 }
00242
00243 L4Re::Vfs::File_system_list
00244 Vfs::file_system_list() noexcept
00245 {
00246     return L4Re::Vfs::File_system_list(_fs_registry);
00247 }
00248
00249 L4Re::Vfs::File_system *
00250 Vfs::get_file_system(char const *fstype) noexcept
00251 {
00252     L4Re::Vfs::File_system *fs;
00253     if ((fs = find_fs_from_type(fstype)))
00254         return fs;
00255
00256     // Try to load a file system module dynamically
00257     int res = Vfs_config::load_module(fstype);
00258     if (res < 0)
00259         return 0;
00260
00261     // Try again
00262     return find_fs_from_type(fstype);
00263 }

```

```

00264
00265 int
00266 Vfs::register_file_factory(cxx::Ref_ptr<L4Re::Vfs::File_factory> f) noexcept
00267 {
00268     if (!f)
00269         return -EINVAL;
00270
00271     void *x = this->malloc(sizeof(File_factory_item));
00272     if (!x)
00273         return -ENOMEM;
00274
00275     auto ff = new (x, cxx::Nothrow()) File_factory_item(f);
00276     _file_factories.push_front(ff);
00277     return 0;
00278 }
00279
00280 int
00281 Vfs::unregister_file_factory(cxx::Ref_ptr<L4Re::Vfs::File_factory> f) noexcept
00282 {
00283     for (auto p: _file_factories)
00284     {
00285         if (p->f == f)
00286         {
00287             _file_factories.remove(p);
00288             p->~File_factory_item();
00289             this->free(p);
00290             return 0;
00291         }
00292     }
00293     return -ENOENT;
00294 }
00295
00296 Ref_ptr<L4Re::Vfs::File_factory>
00297 Vfs::get_file_factory(int proto) noexcept
00298 {
00299     for (auto p: _file_factories)
00300         if (p->f->proto() == proto)
00301             return p->f;
00302
00303     return Ref_ptr<L4Re::Vfs::File_factory>();
00304 }
00305
00306 Ref_ptr<L4Re::Vfs::File_factory>
00307 Vfs::get_file_factory(char const *proto_name) noexcept
00308 {
00309     for (auto p: _file_factories)
00310     {
00311         auto n = p->f->proto_name();
00312         if (n)
00313         {
00314             char const *a = n;
00315             char const *b = proto_name;
00316             for (; *a && *b && *a == *b; ++a, ++b)
00317                 ;
00318
00319             if ((*a == 0) && (*b == 0))
00320                 return p->f;
00321         }
00322     }
00323
00324     return Ref_ptr<L4Re::Vfs::File_factory>();
00325 }
00326
00327 int
00328 Vfs::alloc_fd(Ref_ptr<L4Re::Vfs::File> const &f) noexcept
00329 {
00330     int fd = fds.alloc();
00331     if (fd < 0)
00332         return -EMFILE;
00333
00334     if (f)
00335         fds.set(fd, f);
00336
00337     return fd;
00338 }
00339
00340 Ref_ptr<L4Re::Vfs::File>
00341 Vfs::free_fd(int fd) noexcept
00342 {
00343     Ref_ptr<L4Re::Vfs::File> f = fds.get(fd);
00344
00345     if (!f)
00346         return Ref_ptr<>::Nil;
00347
00348     fds.free(fd);
00349     return f;
00350 }

```

```

00351
00352
00353 Ref_ptr<L4Re::Vfs::File>
00354 Vfs::get_root() noexcept
00355 {
00356     return cxx::ref_ptr(&_root);
00357 }
00358
00359 Ref_ptr<L4Re::Vfs::File>
00360 Vfs::get_cwd() noexcept
00361 {
00362     return _cwd;
00363 }
00364
00365 void
00366 Vfs::set_cwd(Ref_ptr<L4Re::Vfs::File> const &dir) noexcept
00367 {
00368     // FIXME: check for is dir
00369     if (dir)
00370         _cwd = dir;
00371 }
00372
00373 Ref_ptr<L4Re::Vfs::File>
00374 Vfs::get_file(int fd) noexcept
00375 {
00376     return fds.get(fd);
00377 }
00378
00379 cxx::Pair<Ref_ptr<L4Re::Vfs::File>, int>
00380 Vfs::set_fd(int fd, Ref_ptr<L4Re::Vfs::File> const &f) noexcept
00381 {
00382     if (!fds.check_fd(fd))
00383         return cxx::pair(Ref_ptr<L4Re::Vfs::File>(Ref_ptr<>::Nil), EBADF);
00384
00385     Ref_ptr<L4Re::Vfs::File> old = fds.get(fd);
00386     fds.set(fd, f);
00387     return cxx::pair(old, 0);
00388 }
00389
00390
00391 #define GET_FILE_DBG(fd, err) \
00392     Ref_ptr<L4Re::Vfs::File> fi = fds.get(fd); \
00393     if (!fi) \
00394     { \
00395         return -err; \
00396     }
00397
00398 #define GET_FILE(fd, err) \
00399     Ref_ptr<L4Re::Vfs::File> fi = fds.get(fd); \
00400     if (!fi) \
00401         return -err;
00402
00403 void
00404 Vfs::align_mmap_start_and_length(void **start, size_t *length)
00405 {
00406     l4_addr_t const s = reinterpret_cast<l4_addr_t>(*start);
00407     size_t const o = s & (L4_PAGESIZE - 1);
00408
00409     *start = reinterpret_cast<void *>(l4_trunc_page(s));
00410     *length = l4_round_page(*length + o);
00411 }
00412
00413 int
00414 Vfs::munmap_regions(void *start, size_t len)
00415 {
00416     using namespace L4;
00417     using namespace L4Re;
00418
00419     int err;
00420     Cap<Dataspace> ds;
00421     Cap<Rm> r = Env::env()->rm();
00422
00423     if (l4_addr_t(start) & (L4_PAGESIZE - 1))
00424         return -EINVAL;
00425
00426     align_mmap_start_and_length(&start, &len);
00427
00428     while (1)
00429     {
00430         DEBUG_LOG(debug_mmap, {
00431             l4_kd_outstring("DETACH: start = 0x");
00432             l4_kd_outhex32(l4_addr_t(start));
00433             l4_kd_outstring(" len = 0x");
00434             l4_kd_outhex32(len);
00435             l4_kd_outstring("\n");
00436         });
00437         err = r->detach(l4_addr_t(start), len, &ds, This_task);

```



```

00438     if (err < 0)
00439         return err;
00440
00441     switch (err & Rm::Detach_result_mask)
00442     {
00443     case Rm::Split_ds:
00444         if (ds.is_valid())
00445             L4Re::virt_cap_alloc->take(ds);
00446         return 0;
00447     case Rm::Detached_ds:
00448         if (ds.is_valid())
00449             L4Re::virt_cap_alloc->release(ds);
00450         break;
00451     default:
00452         break;
00453     }
00454
00455     if (!(err & Rm::Detach_again))
00456         return 0;
00457 }
00458 }
00459
00460 int
00461 Vfs::munmap(void *start, size_t len) L4_NOTHROW
00462 {
00463     using namespace L4;
00464     using namespace L4Re;
00465
00466     int err = 0;
00467     Cap<Rm> r = Env::env()->rm();
00468
00469     // Fields for obtaining a list of areas for the calling process
00470     long area_cnt = -1;           // No. of areas in this process
00471     Rm::Area const *area_array;
00472     bool matches_area = false;    // true if unmap parameters match an area
00473
00474     // First check if there are any areas matching the munmap request. Those
00475     // might have been created by an mmap call using PROT_NONE as protection
00476     // modifier.
00477
00478     area_cnt = r->get_areas((l4_addr_t) start, &area_array);
00479
00480     // It is enough to check for the very first entry, since get_areas will
00481     // only return areas with a starting address equal or greater to <start>.
00482     // However, we intend to unmap at most the area starting exactly at
00483     // <start>.
00484     if (area_cnt > 0)
00485     {
00486         size_t area_size = area_array[0].end - area_array[0].start + 1;
00487
00488         // Only free the area if the munmap parameters describe it exactly.
00489         if (area_array[0].start == (l4_addr_t) start && area_size == len)
00490         {
00491             r->free_area((l4_addr_t) start);
00492             matches_area = true;
00493         }
00494     }
00495
00496     // After clearing possible area reservations from PROT_NONE mappings, clear
00497     // any regions in the address range specified. Note that errors shall be
00498     // suppressed if an area was freed but no regions were found.
00499     err = munmap_regions(start, len);
00500     if (err == -ENOENT && matches_area)
00501         return 0;
00502
00503     return err;
00504 }
00505
00506 int
00507 Vfs::alloc_ds(unsigned long size, L4Re::Shared_cap<L4Re::Dataspace> *ds)
00508 {
00509     *ds = L4Re::make_shared_cap<L4Re::Dataspace>(L4Re::virt_cap_alloc);
00510
00511     if (!ds->is_valid())
00512         return -ENOMEM;
00513
00514     int err;
00515     if ((err = Vfs_config::allocator()->alloc(size, ds->get())) < 0)
00516         return err;
00517
00518     DEBUG_LOG(debug_mmap, {
00519         l4_kd_outstring("ANON DS ALLOCATED: size=");
00520         l4_kd_outhex32(size);
00521         l4_kd_outstring(" cap = 0x");
00522         l4_kd_outhex32(ds->cap());
00523         l4_kd_outstring("\n");
00524     });

```

```

00525
00526     return 0;
00527 }
00528
00529 int
00530 Vfs::alloc_anon_mem(l4_umword_t size, L4Re::Shared_cap<L4Re::Dataspace> *ds,
00531                    l4_addr_t *offset)
00532 {
00533     #if !defined(CONFIG_MMU)
00534         // Small values for !MMU systems. These platforms do not have much memory
00535         // typically and the memory must be instantly allocated.
00536         enum
00537         {
00538             ANON_MEM_DS_POOL_SIZE = 256UL < 10, // size of a pool dataspace used for anon memory
00539             ANON_MEM_MAX_SIZE     = 32UL < 10, // chunk size that will be allocate a dataspace
00540         };
00541     #elif defined(USE_BIG_ANON_DS)
00542         enum
00543         {
00544             ANON_MEM_DS_POOL_SIZE = 256UL < 20, // size of a pool dataspace used for anon memory
00545             ANON_MEM_MAX_SIZE     = 32UL < 20, // chunk size that will be allocate a dataspace
00546         };
00547     #else
00548         enum
00549         {
00550             ANON_MEM_DS_POOL_SIZE = 256UL < 20, // size of a pool dataspace used for anon memory
00551             ANON_MEM_MAX_SIZE     = 0UL < 20,  // chunk size that will be allocate a dataspace
00552         };
00553     #endif
00554
00555     if (size >= ANON_MEM_MAX_SIZE)
00556     {
00557         int err;
00558         if ((err = alloc_ds(size, ds)) < 0)
00559             return err;
00560
00561         *offset = 0;
00562
00563         if (!_early_oom)
00564             return err;
00565
00566         return (*ds)->allocate(0, size);
00567     }
00568
00569     if (!_anon_ds.is_valid() || _anon_offset + size >= ANON_MEM_DS_POOL_SIZE)
00570     {
00571         int err;
00572         if ((err = alloc_ds(ANON_MEM_DS_POOL_SIZE, ds)) < 0)
00573             return err;
00574
00575         _anon_offset = 0;
00576         _anon_ds = *ds;
00577     }
00578     else
00579         *ds = _anon_ds;
00580
00581     if (_early_oom)
00582     {
00583         if (int err = (*ds)->allocate(_anon_offset, size))
00584             return err;
00585     }
00586
00587     *offset = _anon_offset;
00588     _anon_offset += size;
00589     return 0;
00590 }
00591
00592 int
00593 Vfs::mmap2(void *start, size_t len, int prot, int flags, int fd, off_t page4k_offset,
00594            void **resp_ptr) L4_NOTHROW
00595 {
00596     DEBUG_LOG(debug_mmap, {
00597         l4_kd_outstring("MMAP params: ");
00598         l4_kd_outstring("start = 0x");
00599         l4_kd_outhex32(l4_addr_t(start));
00600         l4_kd_outstring(", len = 0x");
00601         l4_kd_outhex32(len);
00602         l4_kd_outstring(", prot = 0x");
00603         l4_kd_outhex32(prot);
00604         l4_kd_outstring(", flags = 0x");
00605         l4_kd_outhex32(flags);
00606         l4_kd_outstring(", offset = 0x");
00607         l4_kd_outhex32(page4k_offset);
00608         l4_kd_outstring("\n");
00609     });
00610
00611     using namespace L4Re;

```

```

00612     off64_t offset = l4_trunc_page(page4k_offset « 12);
00613
00614     if (flags & MAP_FIXED)
00615         if (l4_addr_t(start) & (L4_PAGESIZE - 1))
00616             return -EINVAL;
00617
00618     align_mmap_start_and_length(&start, &len);
00619
00620     // special code to just reserve an area of the virtual address space
00621     // Same behavior should be exposed when mapping with PROT_NONE. Mind that
00622     // PROT_NONE can only be specified exclusively, since it is defined to 0x0.
00623     if ((flags & 0x1000000) || (prot == PROT_NONE))
00624     {
00625         int err;
00626         L4::Cap<Rm> r = Env::env()->rm();
00627         l4_addr_t area = reinterpret_cast<l4_addr_t>(start);
00628         err = r->reserve_area(&area, len, L4Re::Rm::F::Search_addr);
00629         if (err < 0)
00630             return err;
00631
00632         *resp_ptr = reinterpret_cast<void*>(area);
00633
00634         DEBUG_LOG(debug_mmap, {
00635             l4_kd_outstring(" MMAP reserved area: 0x");
00636             l4_kd_outhex32(area);
00637             l4_kd_outstring(" length= 0x");
00638             l4_kd_outhex32(len);
00639             l4_kd_outstring("\n");
00640         });
00641
00642         return 0;
00643     }
00644
00645     L4Re::Shared_cap<L4Re::Dataspace> ds;
00646     l4_addr_t anon_offset = 0;
00647     L4Re::Rm::Flags rm_flags(0);
00648
00649     if (flags & (MAP_ANONYMOUS | MAP_PRIVATE))
00650     {
00651         rm_flags |= L4Re::Rm::F::Detach_free;
00652
00653         int err = alloc_anon_mem(len, &ds, &anon_offset);
00654         if (err)
00655             return err;
00656
00657         DEBUG_LOG(debug_mmap, {
00658             l4_kd_outstring(" USE ANON MEM: 0x");
00659             l4_kd_outhex32(ds.cap());
00660             l4_kd_outstring(" offs = 0x");
00661             l4_kd_outhex32(anon_offset);
00662             l4_kd_outstring("\n");
00663         });
00664     }
00665
00666     char const *region_name = "[unknown]";
00667     l4_addr_t file_offset = 0;
00668     if (!(flags & MAP_ANONYMOUS))
00669     {
00670         Ref_ptr<L4Re::Vfs::File> fi = fds.get(fd);
00671         if (!fi)
00672             return -EBADF;
00673
00674         region_name = fi->path();
00675
00676         L4::Cap<L4Re::Dataspace> fds = fi->data_space();
00677
00678         if (!fds.is_valid())
00679             return -EINVAL;
00680
00681         if (len + offset > l4_round_page(fds->size()))
00682             return -EINVAL;
00683
00684         if (flags & MAP_PRIVATE)
00685         {
00686             DEBUG_LOG(debug_mmap, l4_kd_outstring("COW\n"));
00687             int err = ds->copy_in(anon_offset, fds, offset, len);
00688             file_offset = offset;
00689             if (err == -L4_EINVAL)
00690             {
00691                 L4::Cap<Rm> r = Env::env()->rm();
00692                 Rm::Unique_region<char*> src;
00693                 Rm::Unique_region<char*> dst;
00694                 err = r->attach(&src, len,
00695                     L4Re::Rm::F::Search_addr | L4Re::Rm::F::R,
00696                     fds, offset);
00697                 if (err < 0)
00698                     return err;

```

```

00699
00700         err = r->attach(&dst, len,
00701                        L4Re::Rm::F::Search_addr | L4Re::Rm::F::RW,
00702                        ds.get(), anon_offset);
00703         if (err < 0)
00704             return err;
00705
00706         memcpy(dst.get(), src.get(), len);
00707
00708         region_name = "[mmap-private]";
00709         file_offset = (unsigned long)dst.get();
00710     }
00711     else if (err)
00712         return err;
00713
00714     offset = anon_offset;
00715 }
00716 else
00717 {
00718     L4Re::virt_cap_alloc->take(fds);
00719     ds = L4Re::Shared_cap<L4Re::Dataspace>(fds, L4Re::virt_cap_alloc);
00720 }
00721 }
00722 else
00723 {
00724     offset = anon_offset;
00725     region_name = "[anon]";
00726     file_offset = offset;
00727 }
00728
00729
00730 if (!(flags & MAP_FIXED) && start == 0)
00731     start = reinterpret_cast<void*>(L4_PAGESIZE);
00732
00733 char *data = static_cast<char *>(start);
00734 L4::Cap<Rm> r = Env::env()->rm();
00735 L4_addr_t overmap_area = L4_INVALID_ADDR;
00736
00737 int err;
00738 if (flags & MAP_FIXED)
00739 {
00740     overmap_area = L4_addr_t(start);
00741
00742     err = r->reserve_area(&overmap_area, len);
00743     if (err < 0)
00744         overmap_area = L4_INVALID_ADDR;
00745
00746     rm_flags |= Rm::F::In_area;
00747
00748     // Make sure to remove old mappings residing at the respective address
00749     // range. If none exists, we are fine as well, allowing us to ignore
00750     // ENOENT here.
00751     err = munmap_regions(start, len);
00752     if (err && err != -ENOENT)
00753         return err;
00754 }
00755
00756 if (!(flags & MAP_FIXED))
00757     rm_flags |= Rm::F::Search_addr;
00758 if (prot & PROT_READ)
00759     rm_flags |= Rm::F::R;
00760 if (prot & PROT_WRITE)
00761     rm_flags |= Rm::F::W;
00762 if (prot & PROT_EXEC)
00763     rm_flags |= Rm::F::X;
00764
00765 err = r->attach(&data, len, rm_flags,
00766               L4::Ipc::make_cap(ds.get(), (prot & PROT_WRITE)
00767                                ? L4_CAP_FPAGE_RW
00768                                : L4_CAP_FPAGE_RO),
00769               offset, L4_PAGESHIFT, L4::Cap<L4::Task>::Invalid,
00770               region_name, file_offset);
00771
00772 DEBUG_LOG(debug_mmap, {
00773     L4_kd_outstring(" MAPPED: 0x");
00774     L4_kd_outhex32(ds.cap());
00775     L4_kd_outstring(" addr: 0x");
00776     L4_kd_outhex32(L4_addr_t(data));
00777     L4_kd_outstring(" bytes: 0x");
00778     L4_kd_outhex32(len);
00779     L4_kd_outstring(" offset: 0x");
00780     L4_kd_outhex32(offset);
00781     L4_kd_outstring(" err = ");
00782     L4_kd_outdec(err);
00783     L4_kd_outstring("\n");
00784 });
00785

```

```

00786
00787     if (overmap_area != L4_INVALID_ADDR)
00788         r->free_area(overmap_area);
00789
00790     if (err < 0)
00791         return err;
00792
00793     l4_assert (!(start && !data));
00794
00795     // release ownership of the attached DS
00796     ds.release();
00797     *resptr = data;
00798
00799     return 0;
00800 }
00801
00802 namespace {
00803     class Auto_area
00804     {
00805     public:
00806         L4::Cap<L4Re::Rm> r;
00807         l4_addr_t a;
00808
00809         explicit Auto_area(L4::Cap<L4Re::Rm> r, l4_addr_t a = L4_INVALID_ADDR)
00810             : r(r), a(a) {}
00811
00812         int reserve(l4_addr_t _a, l4_size_t sz, L4Re::Rm::Flags flags)
00813         {
00814             free();
00815             a = _a;
00816             int e = r->reserve_area(&a, sz, flags);
00817             if (e)
00818                 a = L4_INVALID_ADDR;
00819             return e;
00820         }
00821
00822         void free()
00823         {
00824             if (is_valid())
00825             {
00826                 r->free_area(a);
00827                 a = L4_INVALID_ADDR;
00828             }
00829         }
00830
00831         bool is_valid() const { return a != L4_INVALID_ADDR; }
00832
00833         ~Auto_area() { free(); }
00834     };
00835 }
00836
00837 int
00838 Vfs::mremap(void *old_addr, size_t old_size, size_t new_size, int flags,
00839             void **new_addr) L4_NOTHROW
00840 {
00841     using namespace L4Re;
00842
00843     DEBUG_LOG(debug_mmap, {
00844         l4_kd_outstring("Mremap: addr = 0x");
00845         l4_kd_outhex32((l4_umword_t)old_addr);
00846         l4_kd_outstring(" old_size = 0x");
00847         l4_kd_outhex32(old_size);
00848         l4_kd_outstring(" new_size = 0x");
00849         l4_kd_outhex32(new_size);
00850         l4_kd_outstring("\n");
00851     });
00852
00853     if (flags & MREMAP_FIXED && !(flags & MREMAP_MAYMOVE))
00854         return -EINVAL;
00855
00856     l4_addr_t oa = l4_trunc_page(reinterpret_cast<l4_addr_t>(old_addr));
00857     if (oa != reinterpret_cast<l4_addr_t>(old_addr))
00858         return -EINVAL;
00859
00860     bool const fixed = flags & MREMAP_FIXED;
00861     bool const maymove = flags & MREMAP_MAYMOVE;
00862
00863     L4::Cap<Rm> r = Env::env()->rm();
00864
00865     // sanitize input parameters to multiples of pages
00866     old_size = l4_round_page(old_size);
00867     new_size = l4_round_page(new_size);
00868
00869     if (!fixed)
00870     {
00871         if (new_size < old_size)
00872             {

```

```

00873         *new_addr = old_addr;
00874         return munmap(reinterpret_cast<void*>(oa + new_size),
00875                        old_size - new_size);
00876     }
00877
00878     if (new_size == old_size)
00879     {
00880         *new_addr = old_addr;
00881         return 0;
00882     }
00883 }
00884
00885 Auto_area old_area(r);
00886 int err = old_area.reserve(oa, old_size, L4Re::Rm::Flags(0));
00887 if (err < 0)
00888     return -EINVAL;
00889
00890 l4_addr_t pad_addr;
00891 Auto_area new_area(r);
00892 if (fixed)
00893 {
00894     l4_addr_t na = l4_trunc_page(reinterpret_cast<l4_addr_t>(*new_addr));
00895     if (na != reinterpret_cast<l4_addr_t>(*new_addr))
00896         return -EINVAL;
00897
00898     // check if the current virtual memory area can be expanded
00899     int err = new_area.reserve(na, new_size, L4Re::Rm::Flags(0));
00900     if (err < 0)
00901         return err;
00902
00903     pad_addr = na;
00904     // unmap all stuff and remap ours ....
00905 }
00906 else
00907 {
00908     l4_addr_t ta = oa + old_size;
00909     unsigned long ts = new_size - old_size;
00910     // check if the current virtual memory area can be expanded
00911     long err = new_area.reserve(ta, ts, L4Re::Rm::Flags(0));
00912     if (!maymove && err)
00913         return -ENOMEM;
00914
00915     L4Re::Rm::Offset toffs;
00916     L4Re::Rm::Flags tflags;
00917     L4::Cap<L4Re::Dataspace> tds;
00918
00919     err = r->find(&ta, &ts, &toffs, &tflags, &tds);
00920
00921     // there is enough space to expand the mapping in place
00922     if (err == -ENOENT || (err == 0 && (tflags & Rm::F::In_area)))
00923     {
00924         old_area.free(); // pad at the original address
00925         pad_addr = oa + old_size;
00926         *new_addr = old_addr;
00927     }
00928     else if (!maymove)
00929         return -ENOMEM;
00930     else
00931     {
00932         // search for a new area to remap
00933         err = new_area.reserve(0, new_size, Rm::F::Search_addr);
00934         if (err < 0)
00935             return -ENOMEM;
00936
00937         pad_addr = new_area.a + old_size;
00938         *new_addr = reinterpret_cast<void *>(new_area.a);
00939     }
00940 }
00941
00942 if (old_area.is_valid())
00943 {
00944     unsigned long size = old_size;
00945
00946     l4_addr_t a = old_area.a;
00947     unsigned long s = 1;
00948     L4Re::Rm::Offset o;
00949     L4Re::Rm::Flags f;
00950     L4::Cap<L4Re::Dataspace> ds;
00951
00952     while (r->find(&a, &s, &o, &f, &ds) >= 0 && !(f & Rm::F::In_area))
00953     {
00954         if (a < old_area.a)
00955         {
00956             auto d = old_area.a - a;
00957             a = old_area.a;
00958             s -= d;
00959             o += d;

```

```

00960     }
00961
00962     if (a + s > old_area.a + old_size)
00963         s = old_area.a + old_size - a;
00964
00965     l4_addr_t x = a - old_area.a + new_area.a;
00966
00967     int err = r->attach(&x, s, Rm::F::In_area | f,
00968                       L4::Ipc::make_cap(ds, f.cap_rights()), o);
00969     if (err < 0)
00970         return err;
00971
00972     // count the new attached ds reference
00973     L4Re::virt_cap_alloc->take(ds);
00974
00975     err = r->detach(a, s, &ds, This_task,
00976                   Rm::Detach_exact | Rm::Detach_keep);
00977     if (err < 0)
00978         return err;
00979
00980     switch (err & Rm::Detach_result_mask)
00981     {
00982     case Rm::Split_ds:
00983         // add a reference as we split up a mapping
00984         if (ds.is_valid())
00985             L4Re::virt_cap_alloc->take(ds);
00986         break;
00987     case Rm::Detached_ds:
00988         if (ds.is_valid())
00989             L4Re::virt_cap_alloc->release(ds);
00990         break;
00991     default:
00992         break;
00993     }
00994
00995     if (size <= s)
00996         break;
00997     a += s;
00998     size -= s;
00999     s = 1;
01000 }
01001
01002 old_area.free();
01003 }
01004
01005 if (old_size < new_size)
01006 {
01007     l4_addr_t const pad_sz = new_size - old_size;
01008     l4_addr_t toffs;
01009     L4Re::Shared_cap<L4Re::Dataspace> tds;
01010     int err = alloc_anon_mem(pad_sz, &tds, &toffs);
01011     if (err)
01012         return err;
01013
01014     // FIXME: must get the protection rights from the old
01015     // mapping and use the same here, for now just use RWX
01016     err = r->attach(&pad_addr, pad_sz,
01017                   Rm::F::In_area | Rm::F::Detach_free | Rm::F::RWX,
01018                   L4::Ipc::make_cap_rw(tds.get()), toffs);
01019     if (err < 0)
01020         return err;
01021
01022     // release ownership of tds, the region map is now the new owner
01023     tds.release();
01024 }
01025
01026 return 0;
01027 }
01028
01029 int
01030 Vfs::mprotect(const void * /* a */, size_t /* sz */, int prot) L4_NOTHROW
01031 {
01032     return (prot & PROT_WRITE) ? -ENOSYS : 0;
01033 }
01034
01035 int
01036 Vfs::msync(void *, size_t, int) L4_NOTHROW
01037 { return 0; }
01038
01039 int
01040 Vfs::madvise(void *, size_t, int) L4_NOTHROW
01041 { return 0; }
01042
01043 }
01044
01045 L4Re::Vfs::Ops *_rtld_l4re_env_posix_vfs_ops;
01046 extern void *l4re_env_posix_vfs_ops __attribute__((alias("__rtld_l4re_env_posix_vfs_ops")),

```

```

        visibility("default")));
01047
01048 namespace {
01049     class Real_mount_tree : public L4Re::Vfs::Mount_tree
01050     {
01051     public:
01052         explicit Real_mount_tree(char *n) : Mount_tree(n) {}
01053
01054         void *operator new (size_t size)
01055         { return __rtld_l4re_env_posix_vfs_ops->malloc(size); }
01056
01057         void operator delete (void *mem)
01058         { __rtld_l4re_env_posix_vfs_ops->free(mem); }
01059     };
01060 }
01061
01062 int
01063 Vfs::mount(char const *path, cxx::Ref_ptr<L4Re::Vfs::File> const &dir) noexcept
01064 {
01065     using L4Re::Vfs::File;
01066     using L4Re::Vfs::Mount_tree;
01067     using L4Re::Vfs::Path;
01068
01069     cxx::Ref_ptr<Mount_tree> root = get_root()->mount_tree();
01070     if (!root)
01071         return -EINVAL;
01072
01073     cxx::Ref_ptr<Mount_tree> base;
01074     Path p = root->lookup(Path(path), &base);
01075
01076     while (!p.empty())
01077     {
01078         Path f = p.strip_first();
01079
01080         if (f.empty())
01081             return -EEXIST;
01082
01083         char *name = __rtld_l4re_env_posix_vfs_ops->strndup(f.path(), f.length());
01084         if (!name)
01085             return -ENOMEM;
01086
01087         auto nt = cxx::make_ref_obj<Real_mount_tree>(name);
01088         if (!nt)
01089         {
01090             __rtld_l4re_env_posix_vfs_ops->free(name);
01091             return -ENOMEM;
01092         }
01093
01094         base->add_child_node(nt);
01095         base = nt;
01096
01097         if (p.empty())
01098         {
01099             nt->mount(dir);
01100             return 0;
01101         }
01102     }
01103
01104     return -EINVAL;
01105 }
01106
01107 #undef DEBUG_LOG
01108 #undef GET_FILE_DBG
01109 #undef GET_FILE

```

## 16.255 vfs.h

```

00001 /*
00002  * (c) 2010 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00003  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00004  *      economic rights: Technische Universität Dresden (Germany)
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00008 #pragma once
00009
00010 #include <14/sys/compiler.h>
00011
00012 #include <unistd.h>
00013 #include <stdarg.h>
00014 #include <fcntl.h>
00015 #include <sys/stat.h>
00016 #include <sys/time.h>

```



```

00017 #include <sys/mman.h>
00018 #include <sys/socket.h>
00019 #include <utime.h>
00020 #include <errno.h>
00021
00022 #ifndef AT_FDCWD
00023 # define AT_FDCWD -100
00024 #endif
00025
00026 #ifdef __cplusplus
00027
00028 #include <l4/sys/capability>
00029 #include <l4/re/cap_alloc>
00030 #include <l4/re/dataspace>
00031 #include <l4/cxx/pair>
00032 #include <l4/cxx/ref_ptr>
00033
00034 namespace L4Re {
00035 namespace Vfs {
00036
00037 class Mount_tree;
00038 class File;
00039
00040 class Generic_file
00041 {
00042 public:
00043     enum Ready_type : unsigned
00044     {
00045         Read = 0,
00046         Write,
00047         Exception
00048     };
00049
00050     virtual ~Generic_file() noexcept = 0;
00051
00052     virtual int unlock_all_locks() noexcept = 0;
00053
00054     virtual int fstat(struct stat64 *buf) const noexcept = 0;
00055
00056     virtual int fchmod(mode_t) noexcept = 0;
00057
00058     virtual int get_status_flags() const noexcept = 0;
00059
00060     virtual int set_status_flags(long flags) noexcept = 0;
00061
00062     virtual int utime(const struct utimbuf *) noexcept = 0;
00063     virtual int utimes(const struct timeval [2]) noexcept = 0;
00064     virtual ssize_t readlink(char *, size_t) = 0;
00065
00066     virtual bool check_ready(Ready_type rt) noexcept = 0;
00067 };
00068
00069 inline
00070 Generic_file::~Generic_file() noexcept
00071 {}
00072
00073 class Directory
00074 {
00075 public:
00076     virtual ~Directory() noexcept = 0;
00077
00078     virtual int faccessat(const char *path, int mode, int flags) noexcept = 0;
00079
00080     virtual int mkdir(const char *path, mode_t mode) noexcept = 0;
00081
00082     virtual int unlink(const char *path) noexcept = 0;
00083
00084     virtual int rename(const char *src_path, const char *dst_path) noexcept = 0;
00085
00086     virtual int link(const char *src_path, const char *dst_path) noexcept = 0;
00087
00088     virtual int symlink(const char *src_path, const char *dst_path) noexcept = 0;
00089
00090     virtual int rmdir(const char *path) noexcept = 0;
00091     virtual int openat(const char *path, int flags, mode_t mode,
00092                       cxx::Ref_ptr<File> *f) noexcept = 0;
00093
00094     virtual ssize_t getdents(char *buf, size_t sizebytes) noexcept = 0;
00095
00096     virtual int fchmodat(const char *pathname,
00097                         mode_t mode, int flags) noexcept = 0;
00098
00099     virtual int utimensat(const char *pathname,
00100                          const struct timespec times[2], int flags) noexcept = 0;
00101
00102     virtual int get_entry(const char *, int, mode_t, cxx::Ref_ptr<File> *) noexcept = 0;
00103 };

```

```

00277
00278 inline
00279 Directory::~Directory() noexcept
00280 {}
00281
00287 class Regular_file
00288 {
00289 public:
00290     virtual ~Regular_file() noexcept = 0;
00291
00302     virtual L4::Cap<L4Re::Dataspace> data_space() noexcept = 0;
00303
00313     virtual ssize_t readv(const struct iovec*, int iovcnt) noexcept = 0;
00314
00325     virtual ssize_t writev(const struct iovec*, int iovcnt) noexcept = 0;
00326
00327     virtual ssize_t preadv(const struct iovec *iov, int iovcnt, off64_t offset) noexcept = 0;
00328     virtual ssize_t pwritev(const struct iovec *iov, int iovcnt, off64_t offset) noexcept = 0;
00329
00337     virtual off64_t lseek(off64_t, int) noexcept = 0;
00338
00339
00347     virtual int ftruncate(off64_t pos) noexcept = 0;
00348
00354     virtual int fsync() const noexcept = 0;
00355
00361     virtual int fdatsync() const noexcept = 0;
00362
00372     virtual int get_lock(struct flock64 *lock) noexcept = 0;
00373
00382     virtual int set_lock(struct flock64 *lock, bool wait) noexcept = 0;
00383 };
00384
00385 inline
00386 Regular_file::~Regular_file() noexcept
00387 {}
00388
00389 class Socket
00390 {
00391 public:
00392     virtual ~Socket() noexcept = 0;
00393     virtual int bind(sockaddr const *, socklen_t) noexcept = 0;
00394     virtual int connect(sockaddr const *, socklen_t) noexcept = 0;
00395     virtual ssize_t send(void const *, size_t, int) noexcept = 0;
00396     virtual ssize_t recv(void *, size_t, int) noexcept = 0;
00397     virtual ssize_t sendto(void const *, size_t, int, sockaddr const *, socklen_t) noexcept = 0;
00398     virtual ssize_t recvfrom(void *, size_t, int, sockaddr *, socklen_t *) noexcept = 0;
00399     virtual ssize_t sendmsg(msghdr const *, int) noexcept = 0;
00400     virtual ssize_t recvmsg(msghdr *, int) noexcept = 0;
00401     virtual int getsockopt(int level, int opt, void *, socklen_t *) noexcept = 0;
00402     virtual int setsockopt(int level, int opt, void const *, socklen_t) noexcept = 0;
00403     virtual int listen(int) noexcept = 0;
00404     virtual int accept(sockaddr *addr, socklen_t *) noexcept = 0;
00405     virtual int shutdown(int) noexcept = 0;
00406
00407     virtual int getsockname(sockaddr *, socklen_t *) noexcept = 0;
00408     virtual int getpeername(sockaddr *, socklen_t *) noexcept = 0;
00409 };
00410
00411 inline
00412 Socket::~Socket() noexcept
00413 {}
00414
00420 class Special_file
00421 {
00422 public:
00423     virtual ~Special_file() noexcept = 0;
00424
00435     virtual int ioctl(unsigned long cmd, va_list args) noexcept = 0;
00436 };
00437
00438 inline
00439 Special_file::~Special_file() noexcept
00440 {}
00441
00455 class File :
00456     public Generic_file,
00457     public Regular_file,
00458     public Directory,
00459     public Special_file,
00460     public Socket
00461 {
00462     friend class Mount_tree;
00463
00464 private:
00465     void operator = (File const &);
00466

```

```

00467 protected:
00468     File() noexcept : _ref_cnt(0) {}
00469     File(File const &)
00470     : Generic_file(), Regular_file(), Directory(), Special_file(), _ref_cnt(0)
00471     {}
00472
00473 public:
00474
00475     const char *get_mount(const char *path, cxx::Ref_ptr<File> *dir,
00476                           cxx::Ref_ptr<Mount_tree> *mt = 0) noexcept;
00477
00478     int openat(const char *path, int flags, mode_t mode,
00479               cxx::Ref_ptr<File> *f) noexcept override;
00480
00481     void add_ref() noexcept { ++_ref_cnt; }
00482     int remove_ref() noexcept { return --_ref_cnt; }
00483
00484     virtual ~File() noexcept = 0;
00485
00486     cxx::Ref_ptr<Mount_tree> mount_tree() const noexcept
00487     { return _mount_tree; }
00488
00489     char const *path() const noexcept { return _path; }
00490
00491 private:
00492     int _ref_cnt;
00493     cxx::Ref_ptr<Mount_tree> _mount_tree;
00494     char _path[80] = "";
00495 };
00496
00497 inline
00498 File::~File() noexcept
00499 {}
00500
00501 class Path
00502 {
00503 private:
00504     char const *_p;
00505     unsigned _l;
00506
00507 public:
00508     Path() noexcept : _p(0), _l(0) {}
00509
00510     explicit Path(char const *p) noexcept : _p(p)
00511     { for (_l = 0; *p; ++p, ++_l) ; }
00512
00513     Path(char const *p, unsigned l) noexcept : _p(p), _l(l)
00514     {}
00515
00516     static bool __is_sep(char s) noexcept;
00517
00518     Path cmp_path(char const *prefix) const noexcept;
00519
00520     struct Invalid_ptr;
00521     operator Invalid_ptr const * () const
00522     { return reinterpret_cast<Invalid_ptr const *>(_p); }
00523
00524     unsigned length() const { return _l; }
00525     char const *path() const { return _p; }
00526
00527     bool empty() const { return _l == 0; }
00528
00529     bool is_sep(unsigned offset) const { return __is_sep(_p[offset]); }
00530
00531     bool strip_sep()
00532     {
00533         bool s = false;
00534         for (; __is_sep(*_p) && _l; ++_p, --_l)
00535             s = true;
00536         return s;
00537     }
00538
00539     Path first() const
00540     {
00541         unsigned i;
00542         for (i = 0; i < _l && !is_sep(i); ++i)
00543             ;
00544         return Path(_p, i);
00545     }
00546
00547     Path strip_first()
00548     {
00549         Path r = first();
00550         _p += r.length();
00551         _l -= r.length();
00552         strip_sep();
00553     }

```

```

00554     return r;
00555 }
00556
00557 };
00558
00559
00560 class Mount_tree
00561 {
00562 public:
00563     explicit Mount_tree(char *n) noexcept;
00564
00565     Path lookup(Path const &path, cxx::Ref_ptr<Mount_tree> *mt,
00566                 cxx::Ref_ptr<Mount_tree> *mp = 0) noexcept;
00567
00568     Path find(Path const &p, cxx::Ref_ptr<Mount_tree> *t) noexcept;
00569
00570     cxx::Ref_ptr<File> mount() const
00571     { return _mount; }
00572
00573     void mount(cxx::Ref_ptr<File> const &m)
00574     {
00575         m->_mount_tree = cxx::ref_ptr(this);
00576         _mount = m;
00577     }
00578
00579     static int create_tree(cxx::Ref_ptr<Mount_tree> const &root,
00580                            char const *path,
00581                            cxx::Ref_ptr<File> const &dir) noexcept;
00582
00583     void add_child_node(cxx::Ref_ptr<Mount_tree> const &cld);
00584
00585     virtual ~Mount_tree() noexcept = 0;
00586
00587     void add_ref() noexcept { ++_ref_cnt; }
00588     int remove_ref() noexcept { return --_ref_cnt; }
00589
00590 private:
00591     friend class Real_mount_tree;
00592
00593     int _ref_cnt;
00594     char *_name;
00595     cxx::Ref_ptr<Mount_tree> _cld;
00596     cxx::Ref_ptr<Mount_tree> _sib;
00597     cxx::Ref_ptr<File> _mount;
00598 };
00599
00600 inline
00601 Mount_tree::~Mount_tree() noexcept
00602 {}
00603
00604 inline bool
00605 Path::__is_sep(char s) noexcept
00606 { return s == '/'; }
00607
00608 inline Path
00609 Path::cmp_path(char const *n) const noexcept
00610 {
00611     char const *p = _p;
00612     for (; *p && !__is_sep(*p) && *n; ++p, ++n)
00613         if (*p != *n)
00614             return Path();
00615     if (*n || (*p && !__is_sep(*p)))
00616         return Path();
00617     return Path(p, _l - (p - _p));
00618 }
00619
00620 inline
00621 Mount_tree::Mount_tree(char *n) noexcept
00622 : _ref_cnt(0), _name(n)
00623 {}
00624
00625 inline Path
00626 Mount_tree::find(Path const &p, cxx::Ref_ptr<Mount_tree> *t) noexcept
00627 {
00628     if (!_cld)
00629         return Path();
00630     for (cxx::Ref_ptr<Mount_tree> x = _cld; x; x = x->_sib)
00631     {
00632         Path const r = p.cmp_path(x->_name);
00633         if (r)
00634         {
00635             *t = x;
00636             return r;
00637         }
00638     }

```

```

00647     }
00648     }
00649
00650     return Path();
00651 }
00652
00653 inline Path
00654 Mount_tree::lookup(Path const &path, cxx::Ref_ptr<Mount_tree> *mt,
00655                    cxx::Ref_ptr<Mount_tree> *mp) noexcept
00656 {
00657     cxx::Ref_ptr<Mount_tree> x(this);
00658     Path p = path;
00659
00660     if (p.first().cmp_path("."))
00661         p.strip_first();
00662
00663     Path last_mp = p;
00664
00665     if (mp)
00666         *mp = x;;
00667
00668     while (1)
00669     {
00670         Path r = x->find(p, &x);
00671
00672         if (!r)
00673         {
00674             if (mp)
00675                 return last_mp;
00676
00677             if (mt)
00678                 *mt = x;
00679
00680             return p;
00681         }
00682
00683         r.strip_sep();
00684
00685         if (mp && x->_mount)
00686         {
00687             last_mp = r;
00688             *mp = x;
00689         }
00690
00691         if (r.empty())
00692         {
00693             if (mt)
00694                 *mt = x;
00695
00696             if (mp)
00697                 return last_mp;
00698             else
00699                 return r;
00700         }
00701
00702         p = r;
00703     }
00704 }
00705
00706 inline
00707 void
00708 Mount_tree::add_child_node(cxx::Ref_ptr<Mount_tree> const &cld)
00709 {
00710     cld->_sib = _cld;
00711     _cld = cld;
00712 }
00713
00714 inline
00715 const char *
00716 File::get_mount(const char *path, cxx::Ref_ptr<File> *dir,
00717                cxx::Ref_ptr<Mount_tree> *mt) noexcept
00718 {
00719     if (!_mount_tree)
00720     {
00721         *dir = cxx::ref_ptr(this);
00722         return path;
00723     }
00724
00725     cxx::Ref_ptr<Mount_tree> mp;
00726     Path p = _mount_tree->lookup(Path(path), mt, &mp);
00727     if (mp->mount())
00728     {
00729         *dir = mp->mount();
00730         return p.path();
00731     }
00732     else
00733     {

```

```

00734     *dir = cxx::ref_ptr(this);
00735     return path;
00736 }
00737 }
00738
00739 inline int
00740 File::openat(const char *path, int flags, mode_t mode,
00741             cxx::Ref_ptr<File> *f) noexcept
00742 {
00743     cxx::Ref_ptr<File> dir;
00744     cxx::Ref_ptr<Mount_tree> mt;
00745     char const *m_path = get_mount(path, &dir, &mt);
00746
00747     int res = dir->get_entry(m_path, flags, mode, f);
00748
00749     if (res < 0)
00750         return res;
00751
00752     if (!(*f)->_mount_tree && mt)
00753         (*f)->_mount_tree = mt;
00754
00755     // Debugging {
00756     size_t i = 0;
00757     for (; i < sizeof((*f)->_path) - 1 && path[i]; ++i)
00758         (*f)->_path[i] = path[i];
00759     (*f)->_path[i] = '\0';
00760     // } Debugging
00761
00762     return res;
00763 }
00764
00773 class Mman
00774 {
00775 public:
00777     virtual int mmap2(void *start, size_t len, int prot, int flags, int fd,
00778                     off_t offset, void **ptr) noexcept = 0;
00779
00781     virtual int munmap(void *start, size_t len) noexcept = 0;
00782
00784     virtual int mremap(void *old, size_t old_sz, size_t new_sz, int flags,
00785                     void **new_addr) noexcept = 0;
00786
00788     virtual int mprotect(const void *a, size_t sz, int prot) noexcept = 0;
00789
00791     virtual int msync(void *addr, size_t len, int flags) noexcept = 0;
00792
00794     virtual int madvise(void *addr, size_t len, int advice) noexcept = 0;
00795
00796     virtual ~Mman() noexcept = 0;
00797 };
00798
00799 inline
00800 Mman::~Mman() noexcept {}
00801
00802 class File_factory
00803 {
00804 private:
00805     int _ref_cnt = 0;
00806     int _proto = 0;
00807     char const *_proto_name = 0;
00808
00809     template<typename T> friend struct cxx::Default_ref_counter;
00810     void add_ref() noexcept { ++_ref_cnt; }
00811     int remove_ref() noexcept { return --_ref_cnt; }
00812
00813 public:
00814     explicit File_factory(int proto) : _proto(proto) {}
00815     explicit File_factory(char const *proto_name) : _proto_name(proto_name) {}
00816     File_factory(int proto, char const *proto_name)
00817         : _proto(proto), _proto_name(proto_name)
00818     {}
00819
00820     File_factory(File_factory const &) = delete;
00821     File_factory &operator = (File_factory const &) = delete;
00822
00823     char const *proto_name() const { return _proto_name; }
00824     int proto() const { return _proto; }
00825
00826     virtual ~File_factory() noexcept = 0;
00827     virtual cxx::Ref_ptr<File> create(L4::Cap<void> file) = 0;
00828 };
00829
00830 inline File_factory::~File_factory() noexcept {}
00831
00832 template<typename IFACE, typename IMPL>
00833 class File_factory_t : public File_factory
00834 {

```

```

00835 public:
00836     File_factory_t()
00837     : File_factory(IFACE::Protocol, L4::kobject_typeid<IFACE>()->name())
00838     {}
00839
00840     cxx::Ref_ptr<File> create(L4::Cap<void> file) override
00841     { return cxx::make_ref_obj<IMPL>(L4::cap_cast<IFACE>(file)); }
00842 };
00843
00857 class File_system
00858 {
00859 protected:
00860     File_system *_next;
00861
00862 public:
00863     File_system() noexcept : _next(0) {}
00869     virtual char const *type() const noexcept = 0;
00870
00887     virtual int mount(char const *source, unsigned long mountflags,
00888                      void const *data, cxx::Ref_ptr<File> *dir) noexcept = 0;
00889
00890     virtual ~File_system() noexcept = 0;
00891
00896     File_system *next() const noexcept { return _next; }
00897     File_system *&next() noexcept { return _next; }
00898     void next(File_system *n) noexcept { _next = n; }
00899 };
00900
00901 inline
00902 File_system::~~File_system() noexcept
00903 {}
00904
00905 class File_system_list
00906 {
00907 public:
00908     class Iterator
00909     {
00910     public:
00911         explicit constexpr Iterator(File_system *c = nullptr) : _c(c) {}
00912
00913         Iterator &operator++()
00914         {
00915             if (_c)
00916                 _c = _c->next();
00917             return *this;
00918         }
00919
00920         bool operator==(Iterator const &other) const { return _c == other._c; }
00921         bool operator!=(Iterator const &other) const { return _c != other._c; }
00922         File_system *operator*() const { return _c; }
00923         File_system *operator->() const { return _c; }
00924
00925     private:
00926         File_system *_c;
00927     };
00928
00929     File_system_list(File_system *head) : _head(head) {}
00930
00931     constexpr Iterator begin() const
00932     { return Iterator(_head); }
00933
00934     constexpr Iterator end() const
00935     { return Iterator(); }
00936
00937 private:
00938     File_system *_head;
00939 };
00940
00946 class Fs
00947 {
00948 public:
00954     virtual cxx::Ref_ptr<File> get_file(int fd) noexcept = 0;
00955
00957     virtual cxx::Ref_ptr<File> get_root() noexcept = 0;
00958
00960     virtual cxx::Ref_ptr<File> get_cwd() noexcept { return get_root(); }
00961
00963     virtual void set_cwd(cxx::Ref_ptr<File> const &) noexcept {}
00964
00970     virtual int alloc_fd(cxx::Ref_ptr<File> const &f = cxx::Ref_ptr<>::Nil) noexcept = 0;
00971
00982     virtual cxx::Pair<cxx::Ref_ptr<File>, int>
00983         set_fd(int fd, cxx::Ref_ptr<File> const &f = cxx::Ref_ptr<>::Nil) noexcept = 0;
00984
00990     virtual cxx::Ref_ptr<File> free_fd(int fd) noexcept = 0;
00991
00999     virtual int mount(char const *path, cxx::Ref_ptr<File> const &dir) noexcept = 0;

```

```

01000
01008     virtual int register_file_system(File_system *f) noexcept = 0;
01009
01017     virtual int unregister_file_system(File_system *f) noexcept = 0;
01018
01026     virtual File_system *get_file_system(char const *fstype) noexcept = 0;
01027
01036     virtual File_system_list file_system_list() noexcept = 0;
01037
01041     int mount(char const *source, char const *target,
01042               char const *fstype, unsigned long mountflags,
01043               void const *data) noexcept;
01044
01045     virtual int register_file_factory(cxx::Ref_ptr<File_factory> f) noexcept = 0;
01046     virtual int unregister_file_factory(cxx::Ref_ptr<File_factory> f) noexcept = 0;
01047     virtual cxx::Ref_ptr<File_factory> get_file_factory(int proto) noexcept = 0;
01048     virtual cxx::Ref_ptr<File_factory> get_file_factory(char const *proto_name) noexcept = 0;
01049
01050     virtual ~Fs() = 0;
01051
01052 private:
01053     int mount_one(char const *source, char const *target,
01054                   File_system *fs, unsigned long mountflags,
01055                   void const *data) noexcept;
01056 };
01057
01058 inline int
01059 Fs::mount_one(char const *source, char const *target,
01060               File_system *fs, unsigned long mountflags,
01061               void const *data) noexcept
01062 {
01063     cxx::Ref_ptr<File> dir;
01064     int res = fs->mount(source, mountflags, data, &dir);
01065
01066     if (res < 0)
01067         return res;
01068
01069     return mount(target, dir);
01070 }
01071
01072 inline int
01073 Fs::mount(char const *source, char const *target,
01074           char const *fstype, unsigned long mountflags,
01075           void const *data) noexcept
01076 {
01077     if ( fstype[0] == 'a'
01078         && fstype[1] == 'u'
01079         && fstype[2] == 't'
01080         && fstype[3] == 'o'
01081         && fstype[4] == 0)
01082     {
01083         File_system_list fsl = file_system_list();
01084         for (File_system_list::Iterator c = fsl.begin(); c != fsl.end(); ++c)
01085             if (mount_one(source, target, *c, mountflags, data) == 0)
01086                 return 0;
01087
01088         return -ENODEV;
01089     }
01090
01091     File_system *fs = get_file_system(fstype);
01092
01093     if (!fs)
01094         return -ENODEV;
01095
01096     return mount_one(source, target, fs, mountflags, data);
01097 }
01098
01099 inline
01100 Fs::~Fs()
01101 {}
01102
01109 class Ops : public Mman, public Fs
01110 {
01111 public:
01112     virtual void *malloc(size_t bytes) noexcept = 0;
01113     virtual void free(void *mem) noexcept = 0;
01114     virtual ~Ops() noexcept = 0;
01115
01116     char *strndup(char const *str, unsigned l) noexcept
01117     {
01118         unsigned len;
01119         for (len = 0; str[len] && len < l; ++len)
01120             ;
01121
01122         if (len == 0)
01123             return nullptr;
01124

```



```

01125     ++len;
01126
01127     char *b = static_cast<char *>(this->malloc(len));
01128     if (b == nullptr)
01129         return nullptr;
01130
01131     char *r = b;
01132     for (; len - 1 > 0 && *str; --len, ++b, ++str)
01133         *b = *str;
01134
01135     *b = 0;
01136     return r;
01137 }
01138
01139 };
01140
01141 inline
01142 Ops::~Ops() noexcept
01143 {}
01144
01145 }}
01146
01147 #endif
01148

```

## 16.256 virtio-net

```

00001 // vi:ft=cpp
00002 /* SPDX-License-Identifier: MIT */
00003 /*
00004  * Copyright (C) 2022, 2024-2025 Kernkonzept GmbH.
00005  * Author(s): Stephan Gerhold <stephan.gerhold@kernkonzept.com>
00006  */
00007 #pragma once
00008
00009 #include <cstring>
00010 #include <functional>
00011
00012 #include <l4/cxx/exceptions>
00013 #include <l4/cxx/minmax>
00014 #include <l4/re/dataspace>
00015 #include <l4/re/env>
00016 #include <l4/re/error_helper>
00017 #include <l4/re/util/unique_cap>
00018 #include <l4/sys/consts.h>
00019
00020 #include <l4/l4virtio/client/l4virtio>
00021 #include <l4/l4virtio/l4virtio>
00022 #include <l4/l4virtio/virtio_net.h>
00023 #include <l4/l4virtio/virtqueue>
00024
00025 namespace L4virtio { namespace Driver {
00026
00030 class Virtio_net_device : public L4virtio::Driver::Device
00031 {
00032 public:
00037     struct Packet
00038     {
00039         l4virtio_net_header_t hdr;
00040         l4_uint8_t data[1500 + 14]; /* MTU + Ethernet header */
00041     };
00042
00047     int rx_queue_size() const
00048     { return max_queue_size(0); }
00049
00054     int tx_queue_size() const
00055     { return max_queue_size(1); }
00056
00070     void setup_device(L4::Cap<L4virtio::Device> srvcap,
00071                     L4::Cap<L4Re::Dataspace>
00072                       queue_ds = L4::Cap<L4Re::Dataspace>::Invalid)
00073     {
00074         // Contact device.
00075         driver_connect(srvcap, false);
00076
00077         if (_config->device != L4VIRTIO_ID_NET)
00078             L4Re::chksys(-L4_ENODEV, "Device is not a network device.");
00079
00080         if (_config->num_queues < 2)
00081             L4Re::chksys(-L4_EINVAL, "Invalid number of queues reported.");
00082
00083         auto rxqsz = rx_queue_size();
00084         auto txqsz = tx_queue_size();

```

```

00085
00086 // Allocate memory for RX/TX queue and RX/TX packet buffers
00087 auto rxqoff = 0;
00088 auto txqoff = l4_round_size(rxqoff + rxqsz * _rxq.total_size(rxqsz),
00089                             L4virtio::Virtqueue::Desc_align);
00090 auto rxpktoff = l4_round_size(txqoff + txqsz * _txq.total_size(txqsz),
00091                               L4virtio::Virtqueue::Desc_align);
00092 auto txpktoff = rxpktoff + rxqsz * sizeof(Packet);
00093 auto totalsz = txpktoff + txqsz * sizeof(Packet);
00094
00095 auto *e = L4Re::Env::env();
00096
00097 if (queue_ds)
00098     _queue_ds = L4Re::Util::Unique_cap<L4Re::Dataspace>(queue_ds);
00099 else
00100 {
00101     _queue_ds = L4Re::chkcap(L4Re::Util::make_unique_cap<L4Re::Dataspace>(),
00102                             "Allocate queue dataspace capability");
00103     L4Re::chksys(e->mem_alloc()->alloc(totalsz, _queue_ds.get(),
00104                                         L4Re::Mem_alloc::Continuous
00105                                             | L4Re::Mem_alloc::Pinned),
00106                 "Allocate memory for virtio structures");
00107 }
00108
00109 L4Re::chksys(e->rm()->attach(&_queue_region, totalsz,
00110                             L4Re::Rm::F::Search_addr | L4Re::Rm::F::RW,
00111                             L4::Ipc::make_cap_rw(_queue_ds.get(), 0,
00112                                                     L4_PAGESHIFT),
00113                             "Attach dataspace for virtio structures");
00114
00115 l4_uint64_t devaddr;
00116 L4Re::chksys(register_ds(_queue_ds.get(), 0, totalsz, &devaddr),
00117               "Register queue dataspace with device");
00118
00119 _rxq.init_queue(rxqsz, _queue_region.get() + rxqoff);
00120 _txq.init_queue(txqsz, _queue_region.get() + txqoff);
00121
00122 config_queue(0, rxqsz, devaddr + rxqoff,
00123              devaddr + rxqoff + _rxq.avail_offset(),
00124              devaddr + rxqoff + _rxq.used_offset());
00125 config_queue(1, txqsz, devaddr + txqoff,
00126              devaddr + txqoff + _txq.avail_offset(),
00127              devaddr + txqoff + _txq.used_offset());
00128
00129 _rxpkts = reinterpret_cast<Packet*>(_queue_region.get() + rxpktoff);
00130 _txpkts = reinterpret_cast<Packet*>(_queue_region.get() + txpktoff);
00131
00132 // Prepare descriptors to save work later
00133 for (l4_uint16_t descno = 0; descno < rxqsz; ++descno)
00134 {
00135     auto &desc = _rxq.desc(descno);
00136     desc.addr = L4virtio::Ptr<void>(devaddr + rxpktoff +
00137                                     descno * sizeof(Packet));
00138     desc.len = sizeof(Packet);
00139     desc.flags.write() = 1;
00140 }
00141 for (l4_uint16_t descno = 0; descno < txqsz; ++descno)
00142 {
00143     auto &desc = _txq.desc(descno);
00144     desc.addr = L4virtio::Ptr<void>(devaddr + txpktoff +
00145                                     descno * sizeof(Packet));
00146     desc.len = sizeof(Packet);
00147 }
00148
00149 // Setup notification IRQ
00150 _driver_notification_irq =
00151     L4Re::chkcap(L4Re::Util::make_unique_cap<L4::Irq>(),
00152                 "Allocate notification capability");
00153
00154 L4Re::chksys(l4_error(e->factory()->create(_driver_notification_irq.get())),
00155             "Create irq for notifications from device");
00156
00157 L4Re::chksys(_device->bind(0, _driver_notification_irq.get()),
00158             "Bind driver notification interrupt");
00159
00160 // Finish handshake with device
00161 l4virtio_set_feature(_config->driver_features_map,
00162                     L4VIRTIO_FEATURE_VERSION_1);
00163 l4virtio_set_feature(_config->driver_features_map, L4VIRTIO_NET_F_MAC);
00164 driver_acknowledge();
00165 }
00166
00170 l4virtio_net_config_t const &device_config() const
00171 {
00172     return *_config->device_config<l4virtio_net_config_t>();
00173 }
00174

```

```

00181 int bind_rx_notification_irq(L4::Cap<L4::Thread> thread, l4_umword_t label)
00182 {
00183     return l4_error(_driver_notification_irq->bind_thread(thread, label));
00184 }
00185
00192 Packet &rx_pkt(l4_uint16_t descno)
00193 {
00194     if (descno >= _rxq.num())
00195         throw L4::Bounds_error("Invalid used descriptor number in RX queue");
00196     return _rxpkts[descno];
00197 }
00198
00214 l4_uint16_t wait_rx(l4_uint32_t *len = nullptr)
00215 {
00216     l4_uint16_t descno;
00217     // Wait until used descriptor becomes available.
00218     for (;;)
00219     {
00220         descno = _rxq.find_next_used(len);
00221         if (descno != Virtqueue::Eoq)
00222             break;
00223
00224         L4Re::chksys(_driver_notification_irq->receive(), "Wait for RX");
00225     }
00226
00227     if (len)
00228         // Ensure that the length provided by the device in wait_for_next_used()
00229         // is not larger than the buffer and subtract the length of the header.
00230         *len = cxx::min(*len - sizeof(_rxpkts[0].hdr), sizeof(_rxpkts[0].data));
00231     return descno;
00232 }
00233
00242 void finish_rx(l4_uint16_t descno)
00243 {
00244     _rxq.free_descriptor(descno, descno);
00245 }
00246
00250 void queue_rx()
00251 {
00252     l4_uint16_t descno;
00253     while ((descno = _rxq.alloc_descriptor()) != Virtqueue::Eoq)
00254         _rxq.enqueue_descriptor(descno);
00255     notify(_rxq);
00256 }
00257
00272 bool tx(std::function<l4_uint32_t(Packet&)> prepare)
00273 {
00274     auto descno = _txq.alloc_descriptor();
00275     if (descno == Virtqueue::Eoq)
00276     {
00277         // Try again after cleaning old descriptors that have already been used
00278         free_used_tx_descriptors();
00279         descno = _txq.alloc_descriptor();
00280         if (descno == Virtqueue::Eoq)
00281             return false;
00282     }
00283
00284     auto &pkt = _txpkts[descno];
00285     auto &desc = _txq.desc(descno);
00286     desc.len = sizeof(pkt.hdr) + prepare(pkt);
00287     send(_txq, descno);
00288     return true;
00289 }
00290
00291 private:
00292 void free_used_tx_descriptors()
00293 {
00294     l4_uint16_t used;
00295     while ((used = _txq.find_next_used()) != Virtqueue::Eoq)
00296     {
00297         if (used >= _txq.num())
00298             throw L4::Bounds_error("Invalid used descriptor number in TX queue");
00299         _txq.free_descriptor(used, used);
00300     }
00301 }
00302
00303 private:
00304 L4Re::Util::Unique_cap<L4Re::Dataspace> _queue_ds;
00305 L4Re::Rm::Unique_region<l4_uint8_t *> _queue_region;
00306 L4Re::Util::Unique_cap<L4::Irq> _driver_notification_irq;
00307 L4virtio::Driver::Virtqueue _rxq, _txq;
00308 Packet *_rxpkts, *_txpkts;
00309 };
00310
00311 } }

```

## 16.257 l4virtio

```

00001 // vi:ft=cpp
00002 /* SPDX-License-Identifier: MIT */
00003 /*
00004  * Copyright (C) 2015-2020, 2022, 2024 Kernkonzept GmbH.
00005  * Author(s): Sarah Hoffmann <sarah.hoffmann@kernkonzept.com>
00006  *
00007  */
00008 #pragma once
00009
00010 #include <l4/sys/factory>
00011 #include <l4/sys/semaphore>
00012 #include <l4/re/dataspace>
00013 #include <l4/re/env>
00014 #include <l4/re/util/unique_cap>
00015 #include <l4/re/util/object_registry>
00016 #include <l4/re/error_helper>
00017
00018 #include <l4/util/atomic.h>
00019 #include <l4/util/bitops.h>
00020 #include <l4/l4virtio/l4virtio>
00021 #include <l4/l4virtio/virtqueue>
00022 #include <l4/sys/consts.h>
00023
00024 #include <cstring>
00025
00026 namespace L4virtio { namespace Driver {
00027
00031 class Device
00032 {
00033 public:
00056 void driver_connect(L4::Cap<L4virtio::Device> srvcap, bool manage_notify = true)
00057 {
00058     _device = srvcap;
00059
00060     _next_devaddr = L4_SUPERPAGESIZE;
00061
00062     auto *e = L4Re::Env::env();
00063
00064     // Set up the virtio configuration page.
00065
00066     _config_cap = L4Re::chkcap(L4Re::Util::make_unique_cap<L4Re::Dataspace>(),
00067                                "Allocate config dataspace capability");
00068
00069     l4_addr_t ds_offset;
00070     L4Re::chksys(_device->device_config(_config_cap.get(), &ds_offset),
00071                 "Request virtio config page");
00072
00073     if (ds_offset & ~L4_PAGEMASK)
00074         L4Re::chksys(-L4_EINVAL, "Virtio config page is page aligned.");
00075
00076     L4Re::chksys(e->rm()->attach(&_config, L4_PAGESIZE,
00077                                L4Re::Rm::F::Search_addr | L4Re::Rm::F::RW,
00078                                L4::Ipc::make_cap_rw(_config_cap.get(), ds_offset,
00079                                L4_PAGESHIFT),
00080                                "Attach config dataspace");
00081
00082     if (memcmp(&_config->magic, "virt", 4) != 0)
00083         L4Re::chksys(-L4_ENODEV, "Device config has wrong magic value");
00084
00085     if (_config->version != 2)
00086         L4Re::chksys(-L4_ENODEV, "Invalid virtio version, must be 2");
00087
00088     _device->set_status(0); // reset
00089     int status = L4VIRTIO_STATUS_ACKNOWLEDGE;
00090     _device->set_status(status);
00091
00092     status |= L4VIRTIO_STATUS_DRIVER;
00093     _device->set_status(status);
00094
00095     if (_config->fail_state())
00096         L4Re::chksys(-L4_EIO, "Device failure during initialisation.");
00097
00098     // Set up the interrupt used to notify the device about events.
00099     // (only supporting one interrupt with index 0 at the moment)
00100
00101     _host_irq = L4Re::chkcap(L4Re::Util::make_unique_cap<L4::Irq>(),
00102                             "Allocate host IRQ capability");
00103
00104     L4Re::chksys(_device->device_notification_irq(0, _host_irq.get()),
00105                 "Request device notification interrupt.");
00106
00107     // Set up the interrupt to get notifications from the device.
00108     // (only supporting one interrupt with index 0 at the moment)
00109     if (manage_notify)

```

```

00110     {
00111         _driver_notification =
00112             L4Re::chkcap(L4Re::Util::make_unique_cap<L4::Semaphore>(),
00113                 "Allocate notification capability");
00114
00115         L4Re::chksys(l4_error(e->factory()->create(_driver_notification.get()),
00116             "Create semaphore for notifications from device");
00117
00118         L4Re::chksys(_device->bind(0, _driver_notification.get()),
00119             "Bind driver notification interrupt");
00120     }
00121 }
00122
00129 int bind_notification_irq(unsigned index, L4::Cap<L4::Triggerable> irq) const
00130 { return l4_error(_device->bind(index, irq)); }
00131
00133 bool fail_state() const { return _config->fail_state(); }
00134
00145 bool feature_negotiated(unsigned int feat) const
00146 { return l4virtio_get_feature(_config->driver_features_map, feat); }
00147
00156 int driver_acknowledge()
00157 {
00158     if (!l4virtio_get_feature(_config->dev_features_map,
00159         L4VIRTIO_FEATURE_VERSION_1))
00160         L4Re::chksys(-L4_ENODEV,
00161             "Require Virtio 1.0 device; Legacy device not supported.");
00162
00163     _config->driver_features_map[0] &= _config->dev_features_map[0];
00164     _config->driver_features_map[1] &= _config->dev_features_map[1];
00165
00166     _device->set_status(_config->status | L4VIRTIO_STATUS_FEATURES_OK);
00167
00168     if (!(_config->status & L4VIRTIO_STATUS_FEATURES_OK))
00169         L4Re::chksys(-L4_EINVAL, "Negotiation of device features.");
00170
00171     _device->set_status(_config->status | L4VIRTIO_STATUS_DRIVER_OK);
00172
00173     if (_config->fail_state())
00174         return -L4_EIO;
00175
00176     return L4_EOK;
00177 }
00178
00196 int register_ds(L4::Cap<L4Re::Dataspace> ds, l4_umword_t offset,
00197     l4_umword_t size, l4_uint64_t *devaddr)
00198 {
00199     *devaddr = next_device_address(size);
00200     return _device->register_ds(L4::Ipc::make_cap_rw(ds), *devaddr, offset, size);
00201 }
00202
00212 int config_queue(int num, unsigned size, l4_uint64_t desc_addr,
00213     l4_uint64_t avail_addr, l4_uint64_t used_addr)
00214 {
00215     auto *queueconf = &_amp;config->queues()[num];
00216     queueconf->num = size;
00217     queueconf->desc_addr = desc_addr;
00218     queueconf->avail_addr = avail_addr;
00219     queueconf->used_addr = used_addr;
00220     queueconf->ready = 1;
00221
00222     return _device->config_queue(num);
00223 }
00224
00230 int max_queue_size(int num) const
00231 {
00232     return _config->queues()[num].num_max;
00233 }
00234
00247 int send_and_wait(Virtqueue &queue, l4_uint16_t descno)
00248 {
00249     send(queue, descno);
00250
00251     // wait for a reply, we assume that no other
00252     // request will get in the way.
00253     auto head = wait_for_next_used(queue);
00254
00255     if (head < 0)
00256         return head;
00257
00258     return (head == descno) ? L4_EOK : -L4_EINVAL;
00259 }
00260
00268 int wait(int index) const
00269 {
00270     if (index != 0)
00271         return -L4_EEXIST;

```

```

00272
00273     return l4_ipc_error(_driver_notification->down(), l4_utcb());
00274 }
00275
00291 int wait_for_next_used(Virtqueue &queue, l4_uint32_t *len = nullptr) const
00292 {
00293     while (true)
00294     {
00295         int err = wait(0);
00296
00297         if (err < 0)
00298             return err;
00299
00300         auto head = queue.find_next_used(len);
00301         if (head != Virtqueue::Eoq) // spurious interrupt?
00302             return head;
00303     }
00304 }
00305
00312 void send(Virtqueue &queue, l4_uint16_t descno)
00313 {
00314     queue.enqueue_descriptor(descno);
00315     notify(queue);
00316 }
00317
00318 void notify(Virtqueue &queue)
00319 {
00320     if (!queue.no_notify_host())
00321         _host_irq->trigger();
00322 }
00323
00324 private:
00325 l4_uint64_t next_device_address(l4_umword_t size)
00326 {
00327     l4_umword_t ret;
00328     size = l4_round_page(size);
00329     do
00330     {
00331         ret = _next_devaddr;
00332         if (l4_umword_t(~0) - ret < size)
00333             L4Re::chksys(-L4_ENOMEM, "Out of device address space.");
00334     }
00335     while (!l4util_cmpxchg(&_next_devaddr, ret, ret + size));
00336
00337     return ret;
00338 }
00339
00350 protected:
00351 L4::Cap<L4virtio::Device> _device;
00352 L4Re::Rm::Unique_region<L4virtio::Device::Config_hdr *> _config;
00353 l4_umword_t _next_devaddr;
00354 L4Re::Util::Unique_cap<L4::Semaphore> _driver_notification;
00355
00356 private:
00357 L4Re::Util::Unique_cap<L4::Irq> _host_irq;
00358 L4Re::Util::Unique_cap<L4Re::Dataspace> _config_cap;
00359 };
00360
00361 } }

```

## 16.258 l4virtio

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00002 /* SPDX-License-Identifier: MIT */
00003 /*
00004  * Copyright (C) 2013-2024 Kernkonzept GmbH.
00005  * Author(s): Alexander Warg <alexander.warg@kernkonzept.com>
00006  *             Matthias Lange <matthias.lange@kernkonzept.com>
00007  *
00008  */
00009 #pragma once
00010
00011 #include "virtio.h"
00012 #include <l4/sys/capability>
00013 #include <l4/sys/cxx/ipc_client>
00014 #include <l4/re/dataspace>
00015 #include <l4/sys/irq>
00016 #include <l4/cxx/utils>
00017
00018 namespace L4virtio {
00039 class Device :
00040     public L4::Kobject_t<Device, L4::Icu, L4VIRTIO_PROTOCOL,
00041         L4::Type_info::Demand_t<1> >

```

```

00042 {
00043 public:
00044 typedef l4virtio_config_queue_t Config_queue;
00045 struct Config_hdr : l4virtio_config_hdr_t
00046 {
00047     Config_queue *queues() const
00048     { return l4virtio_config_queues(this); }
00049
00050     template <typename T>
00051     T *device_config() const
00052     {
00053         return static_cast<T*>(l4virtio_device_config(this));
00054     }
00055
00056     int config_queue(unsigned num, L4::Cap<L4::Triggerable> out_notify,
00057                     L4::Cap<L4::Triggerable> in_notify,
00058                     l4_timeout_s to = L4_IPC_TIMEOUT_NEVER)
00059     {
00060         return send_cmd(L4VIRTIO_CMD_CFG_QUEUE | num,
00061                         out_notify, in_notify, to);
00062     }
00063
00064     int notify_queue(unsigned num, L4::Cap<L4::Triggerable> out_notify,
00065                     L4::Cap<L4::Triggerable> in_notify,
00066                     l4_timeout_s to = L4_IPC_TIMEOUT_NEVER)
00067     {
00068         return send_cmd(L4VIRTIO_CMD_NOTIFY_QUEUE | num,
00069                         out_notify, in_notify, to);
00070     }
00071
00080     bool fail_state() const
00081     {
00082         auto cfg_status = cxx::access_once(&status);
00083         return cfg_status
00084             & (L4VIRTIO_STATUS_FAILED | L4VIRTIO_STATUS_DEVICE_NEEDS_RESET);
00085     }
00086
00087     int set_status(unsigned new_status, L4::Cap<L4::Triggerable> out_notify,
00088                  L4::Cap<L4::Triggerable> in_notify,
00089                  l4_timeout_s to = L4_IPC_TIMEOUT_NEVER)
00090     {
00091         return send_cmd(L4VIRTIO_CMD_SET_STATUS | new_status,
00092                         out_notify, in_notify, to);
00093     }
00094
00095     int cfg_changed(unsigned reg, L4::Cap<L4::Triggerable> out_notify,
00096                    L4::Cap<L4::Triggerable> in_notify,
00097                    l4_timeout_s to = L4_IPC_TIMEOUT_NEVER)
00098     {
00099         return send_cmd(L4VIRTIO_CMD_CFG_CHANGED | reg,
00100                         out_notify, in_notify, to);
00101     }
00102
00103     int send_cmd(unsigned command, L4::Cap<L4::Triggerable> out_notify,
00104                  L4::Cap<L4::Triggerable> in_notify,
00105                  l4_timeout_s to = L4_IPC_TIMEOUT_NEVER)
00106     {
00107         cxx::write_now(&cmd, command);
00108
00109         if (out_notify)
00110             out_notify->trigger();
00111
00112         auto utcb = l4_utcb();
00113         auto ipc_to = l4_timeout(L4_IPC_TIMEOUT_0, to);
00114
00115         do
00116         {
00117             if (in_notify)
00118                 if (l4_ipc_error(l4_ipc_receive(in_notify.cap(), utcb, ipc_to),
00119                                utcb) == L4_IPC_RETIMEOUT)
00120                     break;
00121         }
00122         while (cxx::access_once(&cmd));
00123
00124         return cxx::access_once(&cmd) ? -L4_EBUSY : L4_EOK;
00125     }
00126 };
00127
00137 L4_INLINE_RPC_OP(L4VIRTIO_OP_SET_STATUS, long,
00138                 set_status, (unsigned status));
00139
00155 L4_INLINE_RPC_OP(L4VIRTIO_OP_CONFIG_QUEUE, long,
00156                 config_queue, (unsigned queue));
00157
00181 L4_INLINE_RPC_OP(L4VIRTIO_OP_REGISTER_DS, long,
00182                 register_ds, (L4::Ipc::Cap<L4Re::Dataspace> ds_cap,
00183                               l4_uint64_t base, l4_umword_t offset,

```

```

00184             l4_umword_t size));
00185
00194     L4_INLINE_RPC_OP(L4VIRTIO_OP_DEVICE_CONFIG, long, device_config,
00195                     (L4::Ipc::Out<L4::Cap<L4Re::Dataspace> > config_ds,
00196                      l4_addr_t *ds_offset));
00197
00216     L4_INLINE_RPC_OP(L4VIRTIO_OP_GET_DEVICE_IRQ, long, device_notification_irq,
00217                     (unsigned index, L4::Ipc::Out<L4::Cap<L4::Triggerable> > irq));
00218
00219
00220     typedef L4::Typeid::Rpc<set_status_t, config_queue_t, register_ds_t,
00221                             device_config_t, device_notification_irq_t>
00222         Rpcs;
00223 };
00224
00225 }

```

## 16.259 l4virtio

```

00001 // vi:ft=cpp
00002 /* SPDX-License-Identifier: MIT */
00003 /*
00004  * Copyright (C) 2014-2025 Kernkonzept GmbH.
00005  * Author(s): Alexander Warg <alexander.warg@kernkonzept.com>
00006  *           Manuel von Oltersdorff-Kalettkka <manuel.kalettkka@kernkonzept.com>
00007  */
00008 */
00009 #pragma once
00010
00011 #include <algorithm>
00012 #include <limits.h>
00013 #include <memory>
00014 #include <vector>
00015
00016 #include <l4/re/dataspace>
00017 #include <l4/re/util/debug>
00018 #include <l4/re/env>
00019 #include <l4/re/error_helper>
00020 #include <l4/re/rm>
00021 #include <l4/re/util/cap_alloc>
00022 #include <l4/re/util/shared_cap>
00023 #include <l4/re/util/unique_cap>
00024
00025 #include <l4/sys/types.h>
00026 #include <l4/re/util/meta>
00027
00028 #include <l4/cxx/bitfield>
00029 #include <l4/cxx/utls>
00030 #include <l4/cxx/unique_ptr>
00031
00032 #include <l4/sys/cxx/ipc_legacy>
00033
00034 #include "../l4virtio"
00035 #include "virtio"
00036
00040 namespace L4virtio {
00041 namespace Svr {
00042
00052 class Dev_config
00053 {
00054 public:
00055     typedef Dev_status Status;
00056     typedef Dev_features Features;
00057
00058 private:
00059     typedef L4Re::Rm::Unique_region< l4virtio_config_hdr_t*> Cfg_region;
00060     typedef L4Re::Util::Shared_cap<L4Re::Dataspace> Cfg_cap;
00061
00062     l4_uint32_t _vendor, _device, _qoffset, _nqueues;
00063     l4_uint32_t _host_features[sizeof(l4virtio_config_hdr_t::dev_features_map)
00064                                   / sizeof(l4_uint32_t)];
00065     Cfg_cap _ds;
00066     Cfg_region _config;
00067     l4_addr_t _ds_offset = 0;
00068
00069     Status _status{0}; // status shadow, can be trusted by the device model
00070
00071     static l4_uint32_t align(l4_uint32_t x)
00072     { return (x + 0xfU) & ~0xfU; }
00073
00074     void attach_n_init_cfg(Cfg_cap const &cfg, l4_addr_t offset)
00075     {
00076         L4Re::chksys(L4Re::Env::env()->rm()->attach(&_config, L4_PAGESIZE,

```



```

00077                                     L4Re::Rm::F::Search_addr | L4Re::Rm::F::RW,
00078                                     L4::Ipc::make_cap_rw(cfg.get()),
00079                                     offset),
00080         "Attach config space to local address space.");
00081
00082     _config->generation = 0;
00083     memset(_config->driver_features_map, 0, sizeof(_config->driver_features_map));
00084     memset(_host_features, 0, sizeof(_host_features));
00085     set_host_feature(L4VIRTIO_FEATURE_VERSION_1);
00086     reset_hdr();
00087
00088     _ds = cfg;
00089     _ds_offset = offset;
00090 }
00091
00092 protected:
00093     void volatile *get_priv_config() const
00094     {
00095         return l4virtio_device_config(_config.get());
00096     }
00097
00098 public:
00099
00100     Dev_config(l4_uint32_t vendor, l4_uint32_t device,
00101               unsigned cfg_size, l4_uint32_t num_queues = 0)
00102     : _vendor(vendor), _device(device),
00103       _qoffset(0x100 + align(cfg_size)),
00104       _nqueues(num_queues)
00105     {
00106         using L4Re::Dataspace;
00107         using L4Re::chkcapp;
00108         using L4Re::chksys;
00109
00110         if (sizeof(l4virtio_config_queue_t) * _nqueues + _qoffset > L4_PAGESIZE)
00111         {
00112             // too many queues does not fit into our page
00113             _qoffset = 0;
00114             _nqueues = 0;
00115         }
00116
00117         auto cfg = chkcapp(L4Re::Util::make_shared_cap<Dataspace>());
00118         chksys(L4Re::Env::env()->mem_alloc()->alloc(L4_PAGESIZE, cfg.get()));
00119
00120         attach_n_init_cfg(cfg, 0);
00121     }
00122
00123     Dev_config(Cfg_cap const &cfg, l4_addr_t cfg_offset,
00124               l4_uint32_t vendor, l4_uint32_t device,
00125               unsigned cfg_size, l4_uint32_t num_queues = 0)
00126     : _vendor(vendor), _device(device),
00127       _qoffset(0x100 + align(cfg_size)),
00128       _nqueues(num_queues)
00129     {
00130         if (sizeof(l4virtio_config_queue_t) * _nqueues + _qoffset > L4_PAGESIZE)
00131         {
00132             // too many queues does not fit into our page
00133             _qoffset = 0;
00134             _nqueues = 0;
00135         }
00136
00137         attach_n_init_cfg(cfg, cfg_offset);
00138     }
00139
00140     void set_host_feature(unsigned feature)
00141     { l4virtio_set_feature(_host_features, feature); }
00142
00143     void clear_host_feature(unsigned feature)
00144     { l4virtio_clear_feature(_host_features, feature); }
00145
00146     bool get_host_feature(unsigned feature)
00147     { return l4virtio_get_feature(_host_features, feature); }
00148
00149     bool get_guest_feature(unsigned feature)
00150     { return l4virtio_get_feature(_config->driver_features_map, feature); }
00151
00152     l4_uint32_t &host_features(unsigned idx)
00153     { return _host_features[idx]; }
00154
00155     l4_uint32_t host_features(unsigned idx) const
00156     { return _host_features[idx]; }
00157
00158     void set_device_notify_index(unsigned idx)
00159     { _config->cfg_device_notify_index = idx; }
00160
00161     l4_uint32_t num_queues() const
00162     { return _nqueues; }
00163

```

```

00207  l4_uint32_t guest_features(unsigned idx) const
00208  { return _config->driver_features_map[idx]; }
00209
00221  l4_uint32_t negotiated_features(unsigned idx) const
00222  { return _config->driver_features_map[idx] & _host_features[idx]; }
00223
00231  Status status() const { return _status; }
00232
00239  l4_uint32_t get_cmd() const
00240  {
00241      return hdr()->cmd;
00242  }
00243
00250  void reset_cmd()
00251  {
00252      const_cast<l4_uint32_t volatile &>(hdr()->cmd) = 0;
00253  }
00254
00262  void set_status(Status status)
00263  {
00264      _status = status;
00265      const_cast<l4_uint32_t volatile &>(hdr()->status) = status.raw;
00266  }
00267
00274  void add_irq_status(l4_uint32_t status)
00275  {
00276      const_cast<l4_uint32_t volatile &>(hdr()->irq_status) |= status;
00277  }
00278
00285  void set_device_needs_reset()
00286  {
00287      _status.device_needs_reset() = 1;
00288      const_cast<l4_uint32_t volatile &>(hdr()->status) = _status.raw;
00289  }
00290
00295  bool change_queue_config(l4_uint32_t num_queues)
00296  {
00297      if (sizeof(l4virtio_config_queue_t) * num_queues + _qoffset > L4_PAGESIZE)
00298          // too many queues does not fit into our page
00299          return false;
00300
00301      _nqueues = num_queues;
00302      reset_hdr(true);
00303      return true;
00304  }
00305
00312  l4virtio_config_queue_t volatile const *qconfig(unsigned index) const
00313  {
00314      if (L4_UNLIKELY(_qoffset < sizeof (l4virtio_config_hdr_t)))
00315          return 0;
00316
00317      if (L4_UNLIKELY(index >= _nqueues))
00318          return 0;
00319
00320      return reinterpret_cast<l4virtio_config_queue_t const *>
00321          (reinterpret_cast<char *>(_config.get()) + _qoffset) + index;
00322  }
00323
00327  void reset_hdr(bool inc_generation = false) const
00328  {
00329      _config->magic = L4VIRTIO_MAGIC;
00330      _config->version = 2;
00331      _config->device = _device;
00332      _config->vendor = _vendor;
00333      _config->status = 0;
00334      _config->irq_status = 0;
00335      _config->num_queues = _nqueues;
00336      _config->queues_offset = _qoffset;
00337
00338      memcpy(_config->dev_features_map, _host_features,
00339             sizeof(_config->dev_features_map));
00340      wmb();
00341      if (inc_generation)
00342          ++_config->generation;
00343  }
00344
00345
00356  bool reset_queue(unsigned index, unsigned num_max,
00357                  bool inc_generation = false,
00358                  unsigned device_notify_index = 0) const
00359  {
00360      l4virtio_config_queue_t volatile *qc;
00361      // this function is allowed to write to the device config
00362      qc = const_cast<l4virtio_config_queue_t volatile *>(qconfig(index));
00363      if (L4_UNLIKELY(qc == 0))
00364          return false;
00365  }

```

```

00366     qc->num_max = num_max;
00367     qc->num = 0;
00368     qc->ready = 0;
00369     qc->device_notify_index = device_notify_index;
00370     wmb();
00371     if (inc_generation)
00372         ++_config->generation;
00373
00374     return true;
00375 }
00376
00381 l4virtio_config_hdr_t const volatile *hdr() const
00382 { return _config.get(); }
00383
00388 L4::Cap<L4Re::Dataspace> ds() const { return _ds.get(); }
00389
00394 l4_addr_t ds_offset() const
00395 { return _ds_offset; }
00396 };
00397
00398
00399 template<typename PRIV_CONFIG>
00400 class Dev_config_t : public Dev_config
00401 {
00402 public:
00404     typedef PRIV_CONFIG Priv_config;
00405
00417     Dev_config_t(l4_uint32_t vendor, l4_uint32_t device,
00418                 l4_uint32_t num_queues = 0)
00419     : Dev_config(vendor, device, sizeof(PRIV_CONFIG), num_queues)
00420     {}
00421
00432     Dev_config_t(L4Re::Util::Shared_cap<L4Re::Dataspace> const &cfg,
00433                 l4_addr_t cfg_offset, l4_uint32_t vendor, l4_uint32_t device,
00434                 l4_uint32_t num_queues = 0)
00435     : Dev_config(cfg, cfg_offset, vendor, device, sizeof(PRIV_CONFIG),
00436                 num_queues)
00437     {}
00438
00448     Priv_config volatile *priv_config() const
00449     {
00450         return static_cast<Priv_config volatile *>(get_priv_config());
00451     }
00452 };
00453
00454
00455 struct No_custom_data {};
00456
00462 template <typename DATA>
00463 class Driver_mem_region_t : public DATA
00464 {
00465 public:
00466     struct Flags
00467     {
00468         Flags() = default;
00469         explicit Flags(l4_uint32_t raw) : raw(raw) {}
00470
00471         l4_uint32_t raw;
00472         CXX_BITFIELD_MEMBER(0, 0, rw, raw);
00473     };
00474
00475 private:
00477     typedef L4Re::Util::Unique_cap<L4Re::Dataspace> Ds_cap;
00478
00479     l4_uint64_t _drv_base;
00480     l4_uint64_t _trans_offset;
00481     l4_umword_t _size;
00482     Flags      _flags;
00483
00484     Ds_cap     _ds;
00485     l4_addr_t   _ds_offset;
00486
00488     L4Re::Rm::Unique_region<l4_addr_t> _local_base;
00489
00490     template<typename T>
00491     T _local(l4_uint64_t addr) const
00492     {
00493         return reinterpret_cast<T>(addr - _trans_offset);
00494     }
00495
00496 public:
00498     Driver_mem_region_t() : _size(0) {}
00499
00511     Driver_mem_region_t(l4_uint64_t drv_base, l4_umword_t size,
00512                         l4_addr_t offset, Ds_cap &&ds)
00513     : _drv_base(l4_trunc_page(drv_base)), _size(0), _flags(0),
00514       _ds_offset(l4_trunc_page(offset))

```

```

00515 {
00516     using L4Re::chksys;
00517     using L4Re::Env;
00518
00519     L4Re::Dataspace::Stats ds_info = L4Re::Dataspace::Stats();
00520     // Sometimes we work with dataspace that do not implement all dataspace
00521     // methods and return an error instead. An example of such a dataspace is
00522     // io's Vi::System_bus. We detect this case when the info method returns
00523     // -L4_ENOSYS and simply assume the dataspace is good for us.
00524     long err = ds->info(&ds_info);
00525     if (err >= 0)
00526     {
00527         l4_addr_t ds_size = l4_round_page(ds_info.size);
00528
00529         if (ds_size < L4_PAGESIZE)
00530             chksys(-L4_EINVAL, "DS too small");
00531
00532         if (_ds_offset >= ds_size)
00533             chksys(-L4_ERANGE, "offset larger than DS size");
00534
00535         size = l4_round_page(size);
00536         if (size > ds_size)
00537             chksys(-L4_EINVAL, "size larger than DS size");
00538
00539         if (_ds_offset > ds_size - size)
00540             chksys(-L4_EINVAL, "invalid offset or size");
00541
00542         // overflow check
00543         if ((ULONG_MAX - size) < _drv_base)
00544             chksys(-L4_EINVAL, "invalid size");
00545
00546         _flags.rw() = (ds_info.flags & L4Re::Dataspace::F::W).raw != 0;
00547     }
00548     else if (err == -L4_ENOSYS)
00549     {
00550         _flags.rw() = true;
00551     }
00552     else
00553     {
00554         chksys(err, "getting data-space infos");
00555     }
00556
00557     auto f = L4Re::Rm::F::Search_addr | L4Re::Rm::F::R;
00558     if (_flags.rw())
00559         f |= L4Re::Rm::F::W;
00560
00561     // use a big alignment to save PT/TLB entries and kernel memory resources!
00562     chksys(Env::env()->rm()->attach(&_local_base, size, f,
00563                                     L4::Ipc::make_cap(ds.get(), _flags.rw()
00564                                                         ? L4_CAP_FPAGE_RW
00565                                                         : L4_CAP_FPAGE_RO),
00566                                     _ds_offset, L4_SUPERPAGESHIFT));
00567
00568     _size = size;
00569     _ds = cxx::move(ds);
00570     _trans_offset = _drv_base - _local_base.get();
00571 }
00572
00573 bool is_writable() const { return _flags.rw(); }
00574
00575 Flags flags() const { return _flags; }
00576
00577 bool empty() const
00578 { return _size == 0; }
00579
00580 l4_uint64_t drv_base() const { return _drv_base; }
00581
00582 l4_addr_t local_base() const { return _local_base.get(); }
00583
00584 l4_umword_t size() const { return _size; }
00585
00586 l4_addr_t ds_offset() const { return _ds_offset; }
00587
00588 L4::Cap<L4Re::Dataspace> ds() const { return _ds.get(); }
00589
00590 bool contains(l4_uint64_t base, l4_umword_t size) const
00591 {
00592     if (base < _drv_base)
00593         return false;
00594
00595     if (base > _drv_base + _size - 1)
00596         return false;
00597
00598     if (size > _size)
00599         return false;
00600
00601     if (base - _drv_base > _size - size)

```

```

00617         return false;
00618
00619         return true;
00620     }
00621
00622     template<typename T>
00623     T *local(Ptr<T> p) const
00624     { return _local<T*>(p.get()); }
00625 };
00626
00627 typedef Driver_mem_region_t<No_custom_data> Driver_mem_region;
00628
00629 template <typename DATA>
00630 class Driver_mem_list_t
00631 {
00632 public:
00633     typedef Driver_mem_region_t<DATA> Mem_region;
00634
00635 private:
00636     cxx::unique_ptr<Mem_region[]> _l;
00637     unsigned _max;
00638     unsigned _free;
00639
00640 public:
00641     typedef L4Re::Util::Unique_cap<L4Re::Dataspace> Ds_cap;
00642
00643     Driver_mem_list_t() : _max(0), _free(0) {}
00644
00645     void init(unsigned max)
00646     {
00647         _l = cxx::make_unique<Driver_mem_region_t<DATA>[]>(max);
00648         _max = max;
00649         _free = 0;
00650     }
00651
00652     bool full() const
00653     { return _free == _max; }
00654
00655     Mem_region const *add(l4_uint64_t drv_base, l4_umword_t size,
00656                          l4_addr_t offset, Ds_cap &&ds)
00657     {
00658         if (full())
00659             L4Re::chksys(-L4_ENOMEM);
00660
00661         _l[_free++] = Mem_region(drv_base, size, offset, cxx::move(ds));
00662         return &_l[_free - 1];
00663     }
00664
00665     void remove(Mem_region const *r)
00666     {
00667         if (r < &_l[0] || r >= &_l[_free])
00668             L4Re::chksys(-L4_ERANGE);
00669
00670         unsigned idx = r - &_l[0];
00671
00672         for (unsigned i = idx + 1; i < _free - 1; ++i)
00673             _l[i] = cxx::move(_l[i + 1]);
00674
00675         _l[--_free] = Mem_region();
00676     }
00677
00678     Mem_region *find(l4_uint64_t base, l4_umword_t size) const
00679     {
00680         return _find(base, size);
00681     }
00682
00683     void load_desc(Virtqueue::Desc const &desc, Request_processor const *p,
00684                   Virtqueue::Desc const **table) const
00685     {
00686         Mem_region const *r = find(desc.addr.get(), desc.len);
00687         if (L4_UNLIKELY(!r))
00688             throw Bad_descriptor(p, Bad_descriptor::Bad_address);
00689
00690         *table = static_cast<Virtqueue::Desc const *>(r->local(desc.addr));
00691     }
00692
00693     void load_desc(Virtqueue::Desc const &desc, Request_processor const *p,
00694                   Mem_region const **data) const
00695     {
00696         Mem_region const *r = find(desc.addr.get(), desc.len);
00697         if (L4_UNLIKELY(!r))
00698             throw Bad_descriptor(p, Bad_descriptor::Bad_address);
00699
00700         *data = r;
00701     }
00702
00703     template<typename ARG>

```

```

00777 void load_desc(Virtqueue::Desc const &desc, Request_processor const *p,
00778               ARG *data) const
00779 {
00780     Mem_region *r = find(desc.addr.get(), desc.len);
00781     if (L4_UNLIKELY(!r))
00782         throw Bad_descriptor(p, Bad_descriptor::Bad_address);
00783     *data = ARG(r, desc, p);
00784 }
00785
00786 Mem_region *begin() { return &_l[0]; }
00787 Mem_region const *begin() const { return &_l[0]; }
00788
00789 Mem_region *end() { return &_l[_free]; }
00790 Mem_region const *end() const { return &_l[_free]; }
00791
00792 private:
00793 Mem_region *_find(l4_uint64_t base, l4_umword_t size) const
00794 {
00795     for (unsigned i = 0; i < _free; ++i)
00796         if (_l[i].contains(base, size))
00797             return &_l[i];
00798     return 0;
00799 }
00800
00801 };
00802
00803 };
00804
00805 typedef Driver_mem_list_t<No_custom_data> Driver_mem_list;
00806
00807 template<typename DATA>
00808 class Device_t
00809 {
00810 public:
00811     typedef Driver_mem_list_t<DATA> Mem_list;
00812
00813 protected:
00814     Mem_list _mem_info;
00815
00816 private:
00817     Dev_config *_device_config;
00818
00819     using Ds_vector = std::vector<L4::Cap<L4Re::Dataspace>>;
00820     std::shared_ptr<Ds_vector const> _trusted_ds_caps;
00821
00822     bool _trusted_ds_validation_enabled = false;
00823
00824 public:
00825     L4_RPC_LEGACY_DISPATCH(L4virtio::Device);
00826     template<typename IOS> int virtio_dispatch(unsigned r, IOS &ios)
00827     { return dispatch(r, ios); }
00828
00829     virtual void reset() = 0;
00830
00831     virtual bool check_features()
00832     { return true; }
00833
00834     virtual bool check_queues() = 0;
00835
00836     virtual int reconfig_queue(unsigned idx) = 0;
00837
00838     virtual void cfg_changed(unsigned /* reg */) {};
00839
00840     virtual void register_single_driver_irq()
00841     { L4Re::chksys(-L4_ENOSYS, "Legacy single IRQ interface not implemented."); }
00842
00843     virtual void trigger_driver_config_irq() = 0;
00844
00845     virtual L4::Cap<L4::Irq> device_notify_irq() const
00846     {
00847         L4Re::chksys(-L4_ENOSYS, "Legacy single IRQ interface not implemented.");
00848         return L4::Cap<L4::Irq>();
00849     }
00850
00851     virtual void register_driver_irq(unsigned idx)
00852     {
00853         if (idx != 0)
00854             L4Re::chksys(-L4_ENOSYS, "Multi IRQ interface not implemented.");
00855         register_single_driver_irq();
00856     }
00857
00858     virtual L4::Cap<L4::Irq> device_notify_irq(unsigned idx)
00859     {
00860         if (idx != 0)
00861             L4Re::chksys(-L4_ENOSYS, "Multi IRQ interface not implemented.");
00862     }
00863
00864
00865
00866
00867
00868
00869
00870
00871

```

```

00892     return device_notify_irq();
00893 }
00894
00896 virtual unsigned num_events_supported() const
00897 { return 1; }
00898
00899 virtual L4::Ipc_svr::Server_iface *server_iface() const = 0;
00900
00901 // Make it possible to react to changes in the list of memory regions
00902 virtual void check_mem_list() {};
00903
00907 Device_t(Dev_config *dev_config)
00908 : _device_config(dev_config)
00909 {}
00910
00914 Mem_list const *mem_info() const
00915 { return &_amp;_mem_info; };
00916
00917 long op_set_status(L4virtio::Device::Rights, unsigned status)
00918 { return _set_status(status); }
00919
00920 long op_config_queue(L4virtio::Device::Rights, unsigned queue)
00921 {
00922     Dev_config::Status status = _device_config->status();
00923     if (status.fail_state() || !status.acked() || !status.driver())
00924         return -L4_EIO;
00925
00926     return reconfig_queue(queue);
00927 }
00928
00929 long op_register_ds(L4virtio::Device::Rights,
00930                    L4::Ipc::Snd_fpage ds_cap_fp, l4_uint64_t ds_base,
00931                    l4_umword_t offset, l4_umword_t sz)
00932 {
00933     L4Re::Util::Dbg()
00934         .printf("Registering dataspace from 0x%llx with %lu KiB, offset 0x%lx\n",
00935                ds_base, sz » 10, offset);
00936
00937     _check_n_init_shm(ds_cap_fp, ds_base, sz, offset);
00938
00939     return 0;
00940 }
00941
00942 long op_device_config(L4virtio::Device::Rights,
00943                      L4::Ipc::Cap<L4Re::Dataspace> &config_ds,
00944                      l4_addr_t &ds_offset)
00945 {
00946     L4Re::Util::Dbg()
00947         .printf("register client: config DS: %lx\n", _device_config->ds().cap());
00948
00949     config_ds = L4::Ipc::make_cap(_device_config->ds(), L4_CAP_FPAGE_RW);
00950     ds_offset = _device_config->ds_offset();
00951     return 0;
00952 }
00953
00954 long op_device_notification_irq(L4virtio::Device::Rights,
00955                                unsigned idx,
00956                                L4::Ipc::Cap<L4::Triggerable> &irq)
00957 {
00958     auto cap = device_notify_irq(idx);
00959
00960     if (!cap.is_valid())
00961         return -L4_EINVAL;
00962
00963     irq = L4::Ipc::make_cap(cap, L4_CAP_FPAGE_RO);
00964     return L4_EOK;
00965 }
00966
00967 int op_bind(L4::Icu::Rights, l4_umword_t idx, L4::Ipc::Snd_fpage irq_cap_fp)
00968 {
00969     if (idx >= num_events_supported())
00970         return -L4_ERANGE;
00971
00972     if (!irq_cap_fp.cap_received())
00973         return -L4_EINVAL;
00974
00975     register_driver_irq(idx);
00976
00977     return L4_EOK;
00978 }
00979
00980 int op_unbind(L4::Icu::Rights, l4_umword_t, L4::Ipc::Snd_fpage)
00981 {
00982     return -L4_ENOSYS;
00983 }
00984
00985 int op_info(L4::Icu::Rights, L4::Icu::_Info &info)

```

```

00986 {
00987     info.features = 0;
00988     info.nr_irqs = num_events_supported();
00989     info.nr_msis = 0;
00990
00991     return L4_EOK;
00992 }
00993
00994 int op_msi_info(L4::Icu::Rights, l4_umword_t, l4_uint64_t, l4_icu_msi_info_t &)
00995 { return -L4_ENOSYS; }
00996
00997 int op_mask(L4::Icu::Rights, l4_umword_t)
00998 { return -L4_ENOSYS; }
00999
01000 int op_unmask(L4::Icu::Rights, l4_umword_t)
01001 { return -L4_ENOREPLY; }
01002
01003 int op_set_mode(L4::Icu::Rights, l4_umword_t, l4_umword_t)
01004 { return -L4_ENOSYS; }
01005
01019 void reset_queue_config(unsigned idx, unsigned num_max,
01020                        bool inc_generation = false,
01021                        unsigned device_notify_index = 0)
01022 {
01023     _device_config->reset_queue(idx, num_max, inc_generation,
01024                                device_notify_index);
01025 }
01026
01031 void init_mem_info(unsigned num)
01032 {
01033     _mem_info.init(num);
01034 }
01035
01043 void device_error()
01044 {
01045     reset();
01046     _device_config->set_device_needs_reset();
01047
01048     // the device MUST NOT notify the driver before DRIVER_OK.
01049     if (_device_config->status().driver_ok())
01050         trigger_driver_config_irq();
01051 }
01052
01066 bool setup_queue(Virtqueue *q, unsigned qn, unsigned num_max)
01067 {
01068     l4virtio_config_queue_t volatile const *qc;
01069     qc = _device_config->qconfig(qn);
01070     if (L4_UNLIKELY(qc == 0))
01071         return false;
01072
01073     if (!qc->ready)
01074     {
01075         q->disable();
01076         return true;
01077     }
01078
01079     // read to local variables before check
01080     l4_uint32_t num = qc->num;
01081     l4_uint64_t desc = qc->desc_addr;
01082     l4_uint64_t avail = qc->avail_addr;
01083     l4_uint64_t used = qc->used_addr;
01084
01085     if (0)
01086         printf("%p: setup queue: num=0x%x max_num=0x%x desc=0x%llx avail=0x%llx used=0x%llx\n",
01087                this, num, num_max, desc, avail, used);
01088
01089     if (!num || num > num_max)
01090         return false;
01091
01092     // num must be power of two
01093     if (num & (num - 1))
01094         return false;
01095
01096     if (desc & 0xf)
01097         return false;
01098
01099     if (avail & 0x1)
01100         return false;
01101
01102     if (used & 0x3)
01103         return false;
01104
01105     auto const *desc_info = _mem_info.find(desc, Virtqueue::desc_size(num));
01106     if (L4_UNLIKELY(!desc_info))
01107         return false;
01108
01109     auto const *avail_info = _mem_info.find(avail, Virtqueue::avail_size(num));

```



```

01110     if (L4_UNLIKELY(!avail_info))
01111         return false;
01112
01113     auto const *used_info = _mem_info.find(used, Virtqueue::used_size(num));
01114     if (L4_UNLIKELY(!used_info || !used_info->is_writable()))
01115         return false;
01116
01117     L4Re::Util::Dbg()
01118         .printf("shm=[%llx-%llx] local=[%lx-%lx] desc=[%llx-%llx] (%p-%p)\n",
01119             desc_info->drv_base(), desc_info->drv_base() + desc_info->size() - 1,
01120             desc_info->local_base(),
01121             desc_info->local_base() + desc_info->size() - 1,
01122             desc, desc + Virtqueue::desc_size(num),
01123             desc_info->local(Ptr<char>(desc)),
01124             desc_info->local(Ptr<char>(desc)) + Virtqueue::desc_size(num));
01125
01126     L4Re::Util::Dbg()
01127         .printf("shm=[%llx-%llx] local=[%lx-%lx] avail=[%llx-%llx] (%p-%p)\n",
01128             avail_info->drv_base(), avail_info->drv_base() + avail_info->size() - 1,
01129             avail_info->local_base(),
01130             avail_info->local_base() + avail_info->size() - 1,
01131             avail, avail + Virtqueue::avail_size(num),
01132             avail_info->local(Ptr<char>(avail)),
01133             avail_info->local(Ptr<char>(avail)) + Virtqueue::avail_size(num));
01134
01135     L4Re::Util::Dbg()
01136         .printf("shm=[%llx-%llx] local=[%lx-%lx] used=[%llx-%llx] (%p-%p)\n",
01137             used_info->drv_base(), used_info->drv_base() + used_info->size() - 1,
01138             used_info->local_base(),
01139             used_info->local_base() + used_info->size() - 1,
01140             used, used + Virtqueue::used_size(num),
01141             used_info->local(Ptr<char>(used)),
01142             used_info->local(Ptr<char>(used)) + Virtqueue::used_size(num));
01143
01144     q->setup(num, desc_info->local(Ptr<void>(desc)),
01145         avail_info->local(Ptr<void>(avail)),
01146         used_info->local(Ptr<void>(used)));
01147     return true;
01148 }
01149
01150 void check_n_init_shm(L4Re::Util::Unique_cap<L4Re::Dataspace> &&shm,
01151     l4_uint64_t base, l4_umword_t size, l4_addr_t offset)
01152 {
01153     if (_mem_info.full())
01154         L4Re::chksys(-L4_ENOMEM);
01155
01156     auto const *i = _mem_info.add(base, size, offset, cxx::move(shm));
01157     L4Re::Util::Dbg()
01158         .printf("PORT[%p]: DMA guest [%llx-%llx] local [%lx-%lx] offset %lx\n",
01159             this, i->drv_base(), i->drv_base() + i->size() - 1,
01160             i->local_base(),
01161             i->local_base() + i->size() - 1,
01162             i->ds_offset());
01163 }
01164
01173 bool handle_mem_cmd_write()
01174 {
01175     l4_uint32_t cmd = _device_config->get_cmd();
01176     if (L4_LIKELY(!(cmd & L4VIRTIO_CMD_MASK)))
01177         return false;
01178
01179     switch (cmd & L4VIRTIO_CMD_MASK)
01180     {
01181     case L4VIRTIO_CMD_SET_STATUS:
01182         _set_status(cmd & ~L4VIRTIO_CMD_MASK);
01183         break;
01184
01185     case L4VIRTIO_CMD_CFG_QUEUE:
01186         reconfig_queue(cmd & ~L4VIRTIO_CMD_MASK);
01187         break;
01188
01189     case L4VIRTIO_CMD_CFG_CHANGED:
01190         cfg_changed(cmd & ~L4VIRTIO_CMD_MASK);
01191         break;
01192
01193     default:
01194         // unknown command
01195         break;
01196     }
01197
01198     _device_config->reset_cmd();
01199
01200     return true;
01201 }
01202
01206 void enable_trusted_ds_validation()
01207 {

```

```

01208     _trusted_ds_validation_enabled = true;
01209 }
01210
01216 void
01217 add_trusted_dataspaces(std::shared_ptr<Ds_vector const> ds)
01218 {
01219     _trusted_ds_caps = ds;
01220 }
01221
01222
01223 private:
01235 long validate_ds(L4::Cap<L4Re::Dataspace> ds)
01236 {
01237     if (!_trusted_ds_caps)
01238         return -L4_EINVAL;
01239     if (std::any_of(_trusted_ds_caps->cbegin(), _trusted_ds_caps->cend(),
01240         [&ds] (L4::Cap<L4Re::Dataspace> cap)
01241         {
01242             return L4Re::Env::env()->task()
01243                 ->cap_equal(ds, cap).label() == 1;
01244         })
01245     )
01246     {
01247         return L4_EOK;
01248     }
01249     return -L4_EINVAL;
01250 }
01251
01252 void _check_n_init_shm(L4::Ipc::Snd_fpage shm_cap_fp,
01253     l4_uint64_t base, l4_umword_t size, l4_addr_t offset)
01254 {
01255     if (!shm_cap_fp.cap_received())
01256         L4Re::chksys(-L4_EINVAL);
01257
01258     L4Re::Util::Unique_cap<L4Re::Dataspace> ds(
01259         L4Re::chkcap(server_iface()->template_rcv_cap<L4Re::Dataspace>(0)));
01260     L4Re::chksys(server_iface()->realloc_rcv_cap(0));
01261
01262     if (_trusted_ds_validation_enabled)
01263         L4Re::chksys(validate_ds(ds.get()), "Validating the dataspace.");
01264
01265     check_n_init_shm(cxx::move(ds), base, size, offset);
01266
01267     check_mem_list();
01268 }
01269
01270 bool check_features_internal()
01271 {
01272     static_assert(sizeof(l4virtio_config_hdr_t::driver_features_map)
01273         == sizeof(l4virtio_config_hdr_t::dev_features_map),
01274         "Driver and device feature maps must be of the same size");
01275
01276     // From the Virtio 1.0 specification 6.1 Driver Requirements and 6.2 Device
01277     // Requirements: A driver MUST accept VIRTIO_F_VERSION_1 if it is offered.
01278     // A device MUST offer VIRTIO_F_VERSION_1. A device MAY fail to operate
01279     // further if VIRTIO_F_VERSION_1 is not accepted.
01280     //
01281     // The L4virtio implementation does not support legacy interfaces so we
01282     // fail here if the Virtio 1.0 feature was not accepted.
01283     if (!_device_config->get_guest_feature(L4VIRTIO_FEATURE_VERSION_1))
01284         return false;
01285
01286     for (auto i = 0u;
01287         i < sizeof(l4virtio_config_hdr_t::driver_features_map)
01288         / sizeof(l4virtio_config_hdr_t::driver_features_map[0]);
01289         i++)
01290     {
01291         // Driver must not accept features that were not offered by device
01292         if (_device_config->guest_features(i)
01293             & ~_device_config->host_features(i))
01294             return false;
01295     }
01296     return check_features();
01297 }
01298
01300 void check_and_update_status(Dev_config::Status status)
01301 {
01302     // snapshot of current status
01303     Dev_config::Status current_status = _device_config->status();
01304
01305     // handle reset
01306     if (!status.raw)
01307     {
01308         _device_config->set_status(status);
01309         return;
01310     }
01311

```

```

01332 // Do no further processing in case of driver or device failure. If FAILED
01333 // or DEVICE_NEEDS_RESET are set only these fail_state bits will be set in
01334 // addition to the current status bits already set.
01335 if (current_status.fail_state() || status.fail_state())
01336 {
01337     if (current_status.fail_state() != status.fail_state())
01338     {
01339         current_status.fail_state() =
01340             current_status.fail_state() | status.fail_state();
01341         _device_config->set_status(current_status);
01342     }
01343     return;
01344 }
01345
01346 // Enforce init sequence ACKNOWLEDGE, DRIVER, FEATURES_OK, DRIVER_OK.
01347 // We do not enforce that only one additional new bit is set per call.
01348 if (!(status.acked() && status.driver())
01349     || (!status.driver() && status.features_ok())
01350     || (!status.features_ok() && status.driver_ok()))
01351 {
01352     current_status.device_needs_reset() = 1;
01353     _device_config->set_status(current_status);
01354     return;
01355 }
01356
01357 // only check feature compatibility before DRIVER_OK is set
01358 if (status.features_ok() && !status.driver_ok()
01359     && !check_features_internal())
01360     status.features_ok() = 0;
01361
01362 // Note that if FEATURES_OK and DRIVER_OK are both updated to being set
01363 // at the same time the above check_features_internal() is skipped; this is
01364 // considered undefined behaviour but it is not prevented.
01365 if (status.running() && !check_queues())
01366 {
01367     current_status.device_needs_reset() = 1;
01368     _device_config->set_status(current_status);
01369     return;
01370 }
01371
01372 _device_config->set_status(status);
01373 }
01374
01375 int _set_status(unsigned new_status)
01376 {
01377     if (new_status == 0)
01378     {
01379         L4Re::Util::Dbg().printf("Resetting device\n");
01380         reset();
01381         _device_config->reset_hdr(true);
01382     }
01383
01384     Dev_config::Status status(new_status);
01385     check_and_update_status(status);
01386
01387     return 0;
01388 }
01389
01390 };
01391
01392 typedef Device_t<No_custom_data> Device;
01393
01394 } // namespace Svr
01395
01396 }

```

## 16.260 virtio

```

00001 // vi:ft=cpp
00002 /* SPDX-License-Identifier: MIT */
00003 /*
00004  * Copyright (C) 2014-2020, 2023-2025 Kernkonzept GmbH.
00005  * Author(s): Alexander Warg <alexander.warg@kernkonzept.com>
00006  *
00007  */
00008 #pragma once
00009
00010 #include <l4/sys/types.h>
00011 #include <l4/cxx/bitfield>
00012 #include <l4/cxx/minmax>
00013 #include <l4/cxx/utils>
00014
00015 #include <limits.h>

```

```

00016 #include <string.h>
00017 #include <stdio.h>
00018
00019 #include "../virtqueue"
00020
00026 namespace L4virtio {
00027 namespace Svr {
00028
00032 struct Dev_status
00033 {
00034     unsigned char raw;
00035     Dev_status() = default;
00036
00038     explicit Dev_status(l4_uint32_t v) : raw(v) {}
00039
00040     CXX_BITFIELD_MEMBER(0, 0, acked, raw);
00041     CXX_BITFIELD_MEMBER(1, 1, driver, raw);
00042     CXX_BITFIELD_MEMBER(2, 2, driver_ok, raw);
00043     CXX_BITFIELD_MEMBER(3, 3, features_ok, raw);
00044     CXX_BITFIELD_MEMBER(6, 7, fail_state, raw);
00045     CXX_BITFIELD_MEMBER(6, 6, device_needs_reset, raw);
00046     CXX_BITFIELD_MEMBER(7, 7, failed, raw);
00047
00057     bool running() const
00058     {
00059         return (raw == 0xf);
00060     }
00061 };
00062
00066 struct Dev_features
00067 {
00068     l4_uint32_t raw;
00069     Dev_features() = default;
00070
00072     explicit Dev_features(l4_uint32_t v) : raw(v) {}
00073
00074     CXX_BITFIELD_MEMBER(28, 28, ring_indirect_desc, raw);
00075     CXX_BITFIELD_MEMBER(29, 29, ring_event_idx, raw);
00076 };
00077
00078
00087 class Virtqueue : public L4virtio::Virtqueue
00088 {
00089 public:
00093     class Head_desc
00094     {
00095         friend class Virtqueue;
00096     private:
00097         Virtqueue::Desc const *_d;
00098         Head_desc(Virtqueue *r, unsigned i) : _d(r->desc(i)) {}
00099
00100     public:
00102         Head_desc() : _d(0) {}
00103
00105         bool valid() const { return _d; }
00106
00108         explicit operator bool () const
00109         { return valid(); }
00110
00112         Desc const *desc() const
00113         { return _d; }
00114     };
00115
00116     struct Request : Head_desc
00117     {
00118         Virtqueue *ring = nullptr;
00119         Request() = default;
00120     private:
00121         friend class Virtqueue;
00122         Request(Virtqueue *r, unsigned i) : Head_desc(r, i), ring(r) {}
00123     };
00124
00125
00136     Request next_avail()
00137     {
00138         if (L4_LIKELY(_current_avail != _avail->idx))
00139         {
00140             rmb();
00141             unsigned head = _current_avail & _idx_mask;
00142             ++_current_avail;
00143             return Request(this, _avail->ring[head]);
00144         }
00145         return Request();
00146     }
00147
00160     void rewind_avail(Head_desc const &d)
00161     {

```

```

00162     unsigned head_idx = d._d - _desc;
00163     // Calculate the distance between _current_avail and head_idx, taking into
00164     // account that _current_avail might have wrapped around with respect to
00165     // _idx_mask in the meantime.
00166     _current_avail -= (_current_avail - head_idx) & _idx_mask;
00167 }
00168
00175 bool desc_avail() const
00176 {
00177     return _current_avail != _avail->idx;
00178 }
00179
00190 void consumed(Head_desc const &r, l4_uint32_t len = 0)
00191 {
00192     l4_uint16_t i = _used->idx & _idx_mask;
00193     _used->ring[i] = Used_elem(r._d - _desc, len);
00194     wmb();
00195     ++_used->idx;
00196 }
00197
00212 template<typename ITER>
00213 void consumed(ITER const &begin, ITER const &end)
00214 {
00215     l4_uint16_t added = 0;
00216     l4_uint16_t idx = _used->idx;
00217
00218     for (auto elem = begin ; elem != end; ++elem, ++added)
00219         _used->ring[(idx + added) & _idx_mask]
00220             = Used_elem(elem->first._d - _desc, elem->second);
00221
00222     wmb();
00223     _used->idx += added;
00224 }
00225
00239 template<typename QUEUE_OBSERVER>
00240 void finish(Head_desc &d, QUEUE_OBSERVER *o, l4_uint32_t len = 0)
00241 {
00242     consumed(d, len);
00243     o->notify_queue(this);
00244     d._d = 0;
00245 }
00246
00261 template<typename ITER, typename QUEUE_OBSERVER>
00262 void finish(ITER const &begin, ITER const &end, QUEUE_OBSERVER *o)
00263 {
00264     consumed(begin, end);
00265     o->notify_queue(this);
00266 }
00267
00273 void disable_notify()
00274 {
00275     if (L4_LIKELY(ready()))
00276         _used->flags.no_notify() = 1;
00277 }
00278
00284 void enable_notify()
00285 {
00286     if (L4_LIKELY(ready()))
00287         _used->flags.no_notify() = 0;
00288 }
00289
00298 Desc const *desc(unsigned idx) const
00299 { return _desc + idx; }
00300
00301 };
00302
00306 struct Data_buffer
00307 {
00308     char *pos;
00309     l4_uint32_t left;
00310
00311     Data_buffer() = default;
00312
00322 template<typename T>
00323 explicit Data_buffer(T *p)
00324 : pos(reinterpret_cast<char *>(p)), left(sizeof(T))
00325 {}
00326
00336 template<typename T>
00337 void set(T *p)
00338 {
00339     pos = reinterpret_cast<char *>(p);
00340     left = sizeof(T);
00341 }
00342
00354 l4_uint32_t copy_to(Data_buffer *dst, l4_uint32_t max = UINT_MAX)
00355 {

```

```

00356     unsigned long bytes = cxx::min(cxx::min(left, dst->left), max);
00357     memcpy(dst->pos, pos, bytes);
00358     left -= bytes;
00359     pos += bytes;
00360     dst->left -= bytes;
00361     dst->pos += bytes;
00362     return bytes;
00363 }
00364
00375 l4_uint32_t skip(l4_uint32_t bytes)
00376 {
00377     unsigned long b = cxx::min(left, bytes);
00378     left -= b;
00379     pos += b;
00380     return b;
00381 }
00382
00388 bool done() const
00389 { return left == 0; }
00390 };
00391
00392 class Request_processor;
00393
00397 struct Bad_descriptor
00398 {
00400     enum Error
00401     {
00402         Bad_address,
00403         Bad_rights,
00404         Bad_flags,
00405         Bad_next,
00406         Bad_size
00407     };
00408
00410     Request_processor const *proc;
00411
00412     // The error code
00413     Error error;
00414
00421     Bad_descriptor(Request_processor const *proc, Error e)
00422     : proc(proc), error(e)
00423     {}
00424
00430     char const *message() const
00431     {
00432         static char const *const err[] =
00433         {
00434             [Bad_address] = "Descriptor address cannot be translated",
00435             [Bad_rights] = "Insufficient memory access rights",
00436             [Bad_flags] = "Invalid descriptor flags",
00437             [Bad_next] = "The descriptor's `next` index is invalid",
00438             [Bad_size] = "Invalid size of the memory block"
00439         };
00440
00441         if (error >= (sizeof(err) / sizeof(err[0])) || !err[error])
00442             return "Unknown error";
00443
00444         return err[error];
00445     }
00446 };
00447
00448
00472 class Request_processor
00473 {
00474 private:
00476     Virtqueue::Desc const *_table;
00477
00479     Virtqueue::Desc _current;
00480
00482     l4_uint16_t _num;
00483
00484 public:
00500     template<typename DESC_MAN, typename ...ARGS>
00501     void start(DESC_MAN *dm, Virtqueue *ring, Virtqueue::Head_desc const &request, ARGS... args)
00502     {
00503         _current = cxx::access_once(request.desc());
00504
00505         if (_current.flags.indirect())
00506         {
00507             dm->load_desc(_current, this, &_table);
00508             _num = _current.len / sizeof(Virtqueue::Desc);
00509             if (L4_UNLIKELY(!_num))
00510                 throw Bad_descriptor(this, Bad_descriptor::Bad_size);
00511             _current = cxx::access_once(_table);
00512         }
00513     }
00514     else

```

```

00515     {
00516         _table = ring->desc(0);
00517         _num = ring->num();
00518     }
00519
00520     dm->load_desc(_current, this, cxx::forward<ARGS>(args)...);
00521 }
00522
00533 template<typename DESC_MAN, typename ...ARGS>
00534 Virtqueue::Request const &start(DESC_MAN *dm, Virtqueue::Request const &request, ARGS... args)
00535 {
00536     start(dm, request.ring, request, cxx::forward<ARGS>(args)...);
00537     return request;
00538 }
00539
00545 Virtqueue::Desc::Flags current_flags() const
00546 { return _current.flags; }
00547
00553 bool has_more() const
00554 { return _current.flags.next(); }
00555
00569 template<typename DESC_MAN, typename ...ARGS>
00570 bool next(DESC_MAN *dm, ARGS... args)
00571 {
00572     if (!_current.flags.next())
00573         return false;
00574
00575     if (L4_UNLIKELY(_current.next >= _num))
00576         throw Bad_descriptor(this, Bad_descriptor::Bad_next);
00577
00578     _current = cxx::access_once(_table + _current.next);
00579
00580     if (0) // we ignore this for performance reasons
00581         if (L4_UNLIKELY(_current.flags.indirect()))
00582             throw Bad_descriptor(this, Bad_descriptor::Bad_flags);
00583
00584     // must throw an exception in case of a bad descriptor
00585     dm->load_desc(_current, this, cxx::forward<ARGS>(args)...);
00586     return true;
00587 }
00588 };
00589
00590 }
00591 }

```

## 16.261 virtio-block

```

00001 // vi:ft=cpp
00002 /* SPDX-License-Identifier: MIT */
00003 /*
00004  * Copyright (C) 2015-2022, 2024 Kernkonzept GmbH.
00005  * Author(s): Sarah Hoffmann <sarah.hoffmann@kernkonzept.com>
00006  *           Manuel von Oltersdorff-Kalettka <manuel.kalettka@kernkonzept.com>
00007  */
00008 */
00009 #pragma once
00010
00011 #include <l4/sys/factory>
00012 #include <l4/sys/semaphore>
00013 #include <l4/re/dataspace>
00014 #include <l4/re/env>
00015 #include <l4/re/util/unique_cap>
00016 #include <l4/re/util/object_registry>
00017 #include <l4/re/error_helper>
00018
00019 #include <l4/util/atomic.h>
00020 #include <l4/util/bitops.h>
00021 #include <l4/l4virtio/client/l4virtio>
00022 #include <l4/l4virtio/l4virtio>
00023 #include <l4/l4virtio/virtqueue>
00024 #include <l4/l4virtio/virtio_block.h>
00025 #include <l4/sys/consts.h>
00026
00027 #include <cstring>
00028 #include <vector>
00029 #include <functional>
00030
00031 namespace L4virtio { namespace Driver {
00032
00036 class Block_device : public Device
00037 {
00038 public:
00039     typedef std::function<void(unsigned char)> Callback;

```

```

00040
00041 private:
00042     enum { Header_size = sizeof(l4virtio_block_header_t) };
00043
00044     struct Request
00045     {
00046         l4_uint16_t tail;
00047         Callback callback;
00048
00049         Request() : tail(Virtqueue::Eq), callback(0) {}
00050     };
00051
00052 public:
00053     class Handle
00054     {
00055     public:
00056         friend Block_device;
00057         l4_uint16_t head;
00058
00059         explicit Handle(l4_uint16_t descno) : head(descno) {}
00060
00061     public:
00062         Handle() : head(Virtqueue::Eq) {}
00063         bool valid() const { return head != Virtqueue::Eq; }
00064     };
00065
00066 void setup_device(L4::Cap<L4virtio::Device> srvcap, l4_size_t usermem,
00067                 void **userdata, Ptr<void> &user_devaddr,
00068                 L4::Cap<L4Re::Dataspace> qds = L4::Cap<L4Re::Dataspace>(),
00069                 l4_uint32_t fmask0 = -1U, l4_uint32_t fmask1 = -1U)
00070 {
00071     // Contact device.
00072     driver_connect(srvcap);
00073
00074     if (_config->device != L4VIRTIO_ID_BLOCK)
00075         L4Re::chksys(-L4_ENODEV, "Device is not a block device.");
00076
00077     if (_config->num_queues != 1)
00078         L4Re::chksys(-L4_EINVAL, "Invalid number of queues reported.");
00079
00080     // Memory is shared in one large dataspace which contains queues,
00081     // space for header/status and additional user-defined memory.
00082     unsigned queuesz = max_queue_size(0);
00083     l4_size_t totalsz = l4_round_page(usermem);
00084
00085     l4_uint64_t const header_offset =
00086         l4_round_size(_queue.total_size(queuesz),
00087                     l4util_bsr(alignedof(l4virtio_block_header_t)));
00088     l4_uint64_t const status_offset = header_offset + queuesz * Header_size;
00089     l4_uint64_t const usermem_offset = l4_round_page(status_offset + queuesz);
00090
00091     // reserve space for one header/status per descriptor
00092     // TODO Should be reduced to 1/3 but this way no freelist is needed.
00093     totalsz += usermem_offset;
00094
00095     auto *e = L4Re::Env::env();
00096     if (!qds.is_valid())
00097     {
00098         _ds = L4Re::chkcap(L4Re::Util::make_unique_cap<L4Re::Dataspace>(),
00099                         "Allocate queue dataspace capability");
00100         L4Re::chksys(e->mem_alloc()->alloc(totalsz, _ds.get(),
00101                                     L4Re::Mem_alloc::Continuous
00102                                     | L4Re::Mem_alloc::Pinned),
00103                     "Allocate memory for virtio structures");
00104         _queue_ds = _ds.get();
00105     }
00106     else
00107     {
00108         if (qds->size() < totalsz)
00109             L4Re::chksys(-L4_EINVAL, "External queue dataspace too small.");
00110         _queue_ds = qds;
00111     }
00112
00113     // Now sort out which region goes where in the dataspace.
00114     L4Re::chksys(e->rm()->attach(&_queue_region, totalsz,
00115                                L4Re::Rm::F::Search_addr | L4Re::Rm::F::RW,
00116                                L4::Ipc::make_cap_rw(_queue_ds), 0,
00117                                L4_PAGESHIFT),
00118                 "Attach dataspace for virtio structures");
00119
00120     l4_uint64_t devaddr;
00121     L4Re::chksys(register_ds(_queue_ds, 0, totalsz, &devaddr),
00122                 "Register queue dataspace with device");
00123
00124     _queue.init_queue(queuesz, _queue_region.get());
00125
00126     config_queue(0, queuesz, devaddr, devaddr + _queue.avail_offset(),
00127                 devaddr + _queue.used_offset());
00128
00129

```



```

00154     _header_addr = devaddr + header_offset;
00155     _headers = reinterpret_cast<l4virtio_block_header_t *>(_queue_region.get()
00156                                                         + header_offset);
00157
00158
00159     _status_addr = devaddr + status_offset;
00160     _status = _queue_region.get() + status_offset;
00161
00162     user_devaddr = Ptr<void>(devaddr + usermem_offset);
00163     if (userdata)
00164         *userdata = _queue_region.get() + usermem_offset;
00165
00166     // setup the callback mechanism
00167     _pending.assign(queueesz, Request());
00168
00169     // Finish handshake with device.
00170     _config->driver_features_map[0] = fmask0;
00171     _config->driver_features_map[1] = fmask1;
00172     driver_acknowledge();
00173 }
00174
00178 l4virtio_block_config_t const &device_config() const
00179 {
00180     return *_config->device_config<l4virtio_block_config_t>();
00181 }
00182
00191 Handle start_request(l4_uint64_t sector, l4_uint32_t type,
00192                     Callback callback)
00193 {
00194     l4_uint16_t descno = _queue.alloc_descriptor();
00195     if (descno == Virtqueue::Eoq)
00196         return Handle(Virtqueue::Eoq);
00197
00198     L4virtio::Virtqueue::Desc &desc = _queue.desc(descno);
00199     Request &req = _pending[descno];
00200
00201     // setup the header
00202     l4virtio_block_header_t &head = _headers[descno];
00203     head.type = type;
00204     head.ioprio = 0;
00205     head.sector = sector;
00206
00207     // and put it in the descriptor
00208     desc.addr = Ptr<void>(_header_addr + descno * Header_size);
00209     desc.len = Header_size;
00210     desc.flags.raw = 0; // no write, no indirect
00211
00212     req.tail = descno;
00213     req.callback = callback;
00214
00215     return Handle(descno);
00216 }
00217
00229 int add_block(Handle handle, Ptr<void> addr, l4_uint32_t size)
00230 {
00231     l4_uint16_t descno = _queue.alloc_descriptor();
00232     if (descno == Virtqueue::Eoq)
00233         return -L4_EAGAIN;
00234
00235     Request &req = _pending[handle.head];
00236     L4virtio::Virtqueue::Desc &desc = _queue.desc(descno);
00237     L4virtio::Virtqueue::Desc &prev = _queue.desc(req.tail);
00238
00239     prev.next = descno;
00240     prev.flags.next() = true;
00241
00242     desc.addr = addr;
00243     desc.len = size;
00244     desc.flags.raw = 0;
00245     if (_headers[handle.head].type > 0) // write or flush request
00246         desc.flags.write() = true;
00247
00248     req.tail = descno;
00249
00250     return L4_EOK;
00251 }
00252
00265 int send_request(Handle handle)
00266 {
00267     // add the status bit
00268     auto descno = _queue.alloc_descriptor();
00269     if (descno == Virtqueue::Eoq)
00270         return -L4_EAGAIN;
00271
00272     Request &req = _pending[handle.head];
00273     L4virtio::Virtqueue::Desc &desc = _queue.desc(descno);
00274     L4virtio::Virtqueue::Desc &prev = _queue.desc(req.tail);

```

```

00275
00276     prev.next = descno;
00277     prev.flags.next() = true;
00278
00279     desc.addr = Ptr<void>(_status_addr + descno);
00280     desc.len = 1;
00281     desc.flags.raw = 0;
00282     desc.flags.write() = true;
00283
00284     req.tail = descno;
00285
00286     send(_queue, handle.head);
00287
00288     return L4_EOK;
00289 }
00290
00306 int process_request(Handle handle)
00307 {
00308     // add the status bit
00309     auto descno = _queue.alloc_descriptor();
00310     if (descno == Virtqueue::Eoq)
00311         return -L4_EAGAIN;
00312
00313     L4virtio::Virtqueue::Desc &desc = _queue.desc(descno);
00314     L4virtio::Virtqueue::Desc &prev = _queue.desc(_pending[handle.head].tail);
00315
00316     prev.next = descno;
00317     prev.flags.next() = true;
00318
00319     desc.addr = Ptr<void>(_status_addr + descno);
00320     desc.len = 1;
00321     desc.flags.raw = 0;
00322     desc.flags.write() = true;
00323
00324     _pending[handle.head].tail = descno;
00325
00326     int ret = send_and_wait(_queue, handle.head);
00327     unsigned char status = _status[descno];
00328     free_request(handle);
00329
00330     if (ret < 0)
00331         return ret;
00332
00333     switch (status)
00334     {
00335     case L4VIRTIO_BLOCK_S_OK: return L4_EOK;
00336     case L4VIRTIO_BLOCK_S_IOERR: return -L4_EIO;
00337     case L4VIRTIO_BLOCK_S_UNSUPP: return -L4_ENOSYS;
00338     }
00339
00340     return -L4_EINVAL;
00341 }
00342
00343 void free_request(Handle handle)
00344 {
00345     if (handle.head != Virtqueue::Eoq
00346         && _pending[handle.head].tail != Virtqueue::Eoq)
00347         _queue.free_descriptor(handle.head, _pending[handle.head].tail);
00348     _pending[handle.head].tail = Virtqueue::Eoq;
00349 }
00350
00357 void process_used_queue()
00358 {
00359     for (l4_uint16_t descno = _queue.find_next_used();
00360          descno != Virtqueue::Eoq;
00361          descno = _queue.find_next_used()
00362          )
00363     {
00364         if (descno >= _queue.num() || _pending[descno].tail == Virtqueue::Eoq)
00365             L4Re::chksys(-L4_ENOSYS, "Bad descriptor number");
00366
00367         unsigned char status = _status[descno];
00368         free_request(Handle(descno));
00369
00370         if (_pending[descno].callback)
00371             _pending[descno].callback(status);
00372     }
00373 }
00374
00375 protected:
00376     L4Re::Util::Unique_cap<L4Re::Dataspace> _ds;
00377     L4Re::Cap<L4Re::Dataspace> _queue_ds;
00378
00379 private:
00380     L4Re::Rm::Unique_region<unsigned char *> _queue_region;
00381     l4virtio_block_header_t *_headers;
00382     unsigned char *_status;

```

```

00383     l4_uint64_t _header_addr;
00384     l4_uint64_t _status_addr;
00385     Virtqueue _queue;
00386     std::vector<Request> _pending;
00387 };
00388
00389 } }
```

## 16.262 virtio-block

```

00001 // vi:ft=cpp
00002 /* SPDX-License-Identifier: MIT */
00003 /*
00004  * Copyright (C) 2017-2021, 2024-2025 Kernkonzept GmbH.
00005  * Author(s): Sarah Hoffmann <sarah.hoffmann@kernkonzept.com>
00006  */
00007 #pragma once
00008
00009 #include <l4/cxx/unique_ptr>
00010 #include <l4/re/util/unique_cap>
00011 #include <climits>
00012
00013 #include <l4/l4virtio/virtio.h>
00014 #include <l4/l4virtio/virtio_block.h>
00015 #include <l4/l4virtio/server/l4virtio>
00016 #include <l4/sys/cxx/ipc_epiface>
00017
00018 namespace L4virtio { namespace Svr {
00019
00020     template <typename Ds_data> class Block_dev_base;
00021
00022     template <typename Ds_data>
00023     class Block_request
00024     {
00025     public:
00026         friend class Block_dev_base<Ds_data>;
00027         enum { Header_size = sizeof(l4virtio_block_header_t) };
00028
00029         struct Data_block
00030         {
00031             Driver_mem_region_t<Ds_data> *mem;
00032             void *addr;
00033             l4_uint32_t len;
00034
00035             Data_block() = default;
00036
00037             Data_block(Driver_mem_region_t<Ds_data> *m, Virtqueue::Desc const &desc,
00038                       Request_processor const *)
00039             : mem(m), addr(m->local(desc.addr)), len(desc.len)
00040             {}
00041         };
00042
00043         unsigned data_size() const
00044         {
00045             Request_processor rp;
00046             Data_block data;
00047
00048             rp.start(_mem_list, _request, &data);
00049
00050             unsigned total = data.len;
00051
00052             try
00053             {
00054                 while (rp.has_more())
00055                 {
00056                     rp.next(_mem_list, &data);
00057                     total += data.len;
00058                 }
00059             }
00060             catch (Bad_descriptor const &e)
00061             {
00062                 // need to convert the exception because e contains a raw pointer to rp
00063                 throw L4::Runtime_error(-L4_EIO, "bad virtio descriptor");
00064             }
00065
00066             if (total < Header_size + 1)
00067                 throw L4::Runtime_error(-L4_EIO, "virtio request too short");
00068
00069             return total - Header_size - 1;
00070         }
00071     };
00072 }
```

```

00090     }
00091
00095     bool has_more()
00096     {
00097         // peek into the remaining data
00098         while (_data.len == 0 && _rp.has_more())
00099             _rp.next(_mem_list, &_data);
00100
00101         // there always must be one byte left for status
00102         return (_data.len > 1 || _rp.has_more());
00103     }
00104
00113     Data_block next_block()
00114     {
00115         Data_block out;
00116
00117         if (_data.len == 0)
00118         {
00119             if (!_rp.has_more())
00120                 throw L4::Runtime_error(-L4_EEXIST,
00121                                         "No more data blocks in virtio request");
00122
00123             if (_todo_blocks == 0)
00124                 throw Bad_descriptor(&_rp, Bad_descriptor::Bad_size);
00125             --_todo_blocks;
00126
00127             _rp.next(_mem_list, &_data);
00128         }
00129
00130         if (_data.len > _max_block_size)
00131             throw Bad_descriptor(&_rp, Bad_descriptor::Bad_size);
00132
00133         out = _data;
00134
00135         if (!_rp.has_more())
00136         {
00137             --(out.len);
00138             _data.len = 1;
00139             _data.addr = static_cast<char *>(_data.addr) + out.len;
00140         }
00141         else
00142             _data.len = 0; // is consumed
00143
00144         return out;
00145     }
00146
00148     l4virtio_block_header_t const &header() const
00149     { return _header; }
00150
00151 private:
00152     Block_request(Virtqueue::Request req, Driver_mem_list_t<Ds_data> *mem_list,
00153                  unsigned max_blocks, l4_uint32_t max_block_size)
00154     : _mem_list(mem_list),
00155       _request(req),
00156       _todo_blocks(max_blocks),
00157       _max_block_size(max_block_size)
00158     {
00159         // read header which should be in the first block
00160         _rp.start(mem_list, _request, &_data);
00161         --_todo_blocks;
00162
00163         if (_data.len < Header_size)
00164             throw Bad_descriptor(&_rp, Bad_descriptor::Bad_size);
00165
00166         _header = *(static_cast<l4virtio_block_header_t *>(_data.addr));
00167         _data.addr = static_cast<char *>(_data.addr) + Header_size;
00168         _data.len -= Header_size;
00169
00170         // if there is no space for status bit we cannot really recover
00171         if (!_rp.has_more() && _data.len == 0)
00172             throw Bad_descriptor(&_rp, Bad_descriptor::Bad_size);
00173     }
00174
00175     int release_request(Virtqueue *queue, l4_uint8_t status, unsigned sz)
00176     {
00177         // write back status
00178         // If there was an error on the way or the status byte is in its
00179         // own block, fast-forward to the last block.
00180         if (_rp.has_more())
00181         {
00182             while (_rp.next(_mem_list, &_data) && _todo_blocks > 0)
00183                 --_todo_blocks;
00184
00185             if (_todo_blocks > 0 && _data.len > 0)
00186                 *(static_cast<l4_uint8_t *>(_data.addr) + _data.len - 1) = status;
00187             else

```

Generated for L4Re by Doxygen

```

00319     pc->geometry.heads = heads;
00320     pc->geometry.sectors = sectors;
00321     Block_features df = device_features();
00322     df.geometry() = true;
00323     set_device_features(df);
00324 }
00325
00332 void set_blk_size(l4_uint32_t sz)
00333 {
00334     _dev_config.priv_config()->blk_size = sz;
00335     Block_features df = device_features();
00336     df.blk_size() = true;
00337     set_device_features(df);
00338 }
00339
00348 void set_topology(l4_uint8_t physical_block_exp,
00349                  l4_uint8_t alignment_offset,
00350                  l4_uint32_t min_io_size,
00351                  l4_uint32_t opt_io_size)
00352 {
00353     l4virtio_block_config_t volatile *pc = _dev_config.priv_config();
00354     pc->topology.physical_block_exp = physical_block_exp;
00355     pc->topology.alignment_offset = alignment_offset;
00356     pc->topology.min_io_size = min_io_size;
00357     pc->topology.opt_io_size = opt_io_size;
00358     Block_features df = device_features();
00359     df.topology() = true;
00360     set_device_features(df);
00361 }
00362
00364 void set_flush()
00365 {
00366     Block_features df = device_features();
00367     df.flush() = true;
00368     set_device_features(df);
00369 }
00370
00375 void set_config_wce(l4_uint8_t writeback)
00376 {
00377     l4virtio_block_config_t volatile *pc = _dev_config.priv_config();
00378     pc->writeback = writeback;
00379     Block_features df = device_features();
00380     df.config_wce() = true;
00381     set_device_features(df);
00382 }
00383
00388 l4_uint8_t get_writeback()
00389 {
00390     l4virtio_block_config_t volatile *pc = _dev_config.priv_config();
00391     return pc->writeback;
00392 }
00393
00402 void set_discard(l4_uint32_t max_discard_sectors, l4_uint32_t max_discard_seg,
00403                 l4_uint32_t discard_sector_alignment)
00404 {
00405     l4virtio_block_config_t volatile *pc = _dev_config.priv_config();
00406     pc->max_discard_sectors = max_discard_sectors;
00407     pc->max_discard_seg = max_discard_seg;
00408     pc->discard_sector_alignment = discard_sector_alignment;
00409     Block_features df = device_features();
00410     df.discard() = true;
00411     set_device_features(df);
00412 }
00413
00422 void set_write_zeroes(l4_uint32_t max_write_zeroes_sectors,
00423                      l4_uint32_t max_write_zeroes_seg,
00424                      l4_uint8_t write_zeroes_may_unmap)
00425 {
00426     l4virtio_block_config_t volatile *pc = _dev_config.priv_config();
00427     pc->max_write_zeroes_sectors = max_write_zeroes_sectors;
00428     pc->max_write_zeroes_seg = max_write_zeroes_seg;
00429     pc->write_zeroes_may_unmap = write_zeroes_may_unmap;
00430     Block_features df = device_features();
00431     df.write_zeroes() = true;
00432     set_device_features(df);
00433 }
00434
00435 public:
00444 Block_dev_base(l4_uint32_t vendor, unsigned queue_size, l4_uint64_t capacity,
00445               bool read_only)
00446 : L4virtio::Svr::Device_t<Ds_data>(&_dev_config),
00447   _vq_max(queue_size),
00448   _dev_config(vendor, L4VIRTIO_ID_BLOCK, 1)
00449 {
00450     this->reset_queue_config(0, queue_size);
00451
00452     Block_features df(0);

```

```

00453     df.ring_indirect_desc() = true;
00454     df.ro() = read_only;
00455     set_device_features(df);
00456
00457     _dev_config.set_host_feature(L4VIRTIO_FEATURE_VERSION_1);
00458
00459     _dev_config.priv_config()->capacity = capacity;
00460 }
00461
00465 virtual void reset_device() = 0;
00466
00470 virtual bool queue_stopped() = 0;
00471
00483 void finalize_request(cxx::unique_ptr<Request> req, unsigned sz,
00484                      l4_uint8_t status = L4VIRTIO_BLOCK_S_OK)
00485 {
00486     if (_dev_config.status().fail_state() || !_queue.ready())
00487         return;
00488
00489     if (req->release_request(&_queue, status, sz) < 0)
00490         this->device_error();
00491
00492     if (!_queue.no_notify_guest())
00493         return;
00494
00495     _dev_config.add_irq_status(L4VIRTIO_IRQ_STATUS_VRING);
00496     _kick_guest_irq->trigger();
00497
00498     // Request can be dropped here.
00499 }
00500
00501 int reconfig_queue(unsigned idx) override
00502 {
00503     if (idx == 0 && this->setup_queue(&_queue, 0, _vq_max))
00504         return 0;
00505
00506     return -L4_EINVAL;
00507 }
00508
00509 void reset() override
00510 {
00511     _queue.disable();
00512     _dev_config.reset_queue(0, _vq_max);
00513     _dev_config.reset_hdr();
00514     reset_device();
00515 }
00516
00517 protected:
00518 bool check_for_new_requests()
00519 {
00520     if (!_queue.ready() || queue_stopped())
00521         return false;
00522
00523     if (_dev_config.status().fail_state())
00524         return false;
00525
00526     return _queue.desc_avail();
00527 }
00528
00530 cxx::unique_ptr<Request> get_request()
00531 {
00532     cxx::unique_ptr<Request> req;
00533
00534     if (!_queue.ready() || queue_stopped())
00535         return req;
00536
00537     if (_dev_config.status().fail_state())
00538         return req;
00539
00540     auto r = _queue.next_avail();
00541     if (!r)
00542         return req;
00543
00544     try
00545     {
00546         cxx::unique_ptr<Request> cur{
00547             new Request(r, &(this->_mem_info), _vq_max, _max_block_size)};
00548         req = cxx::move(cur);
00549     }
00550
00551     catch (Bad_descriptor const &e)
00552     {
00553         this->device_error();
00554         return req;
00555     }
00556
00557     return req;

```

```

00558     }
00559
00560 private:
00561     void register_single_driver_irq() override
00562     {
00563         _kick_guest_irq = L4Re::Util::Unique_cap<L4::Irq>(
00564             L4Re::chkcap(this->server_iface()->template rcv_cap<L4::Irq>(0)));
00565
00566         L4Re::chksys(this->server_iface()->realloc_rcv_cap(0));
00567     }
00568
00569     void trigger_driver_config_irq() override
00570     {
00571         _dev_config.add_irq_status(L4VIRTIO_IRQ_STATUS_CONFIG);
00572         _kick_guest_irq->trigger();
00573     }
00574
00575     bool check_queues() override
00576     {
00577         if (!_queue.ready())
00578         {
00579             reset();
00580             return false;
00581         }
00582
00583         return true;
00584     }
00585 };
00586
00587 template <typename Ds_data>
00588 struct Block_dev
00589 : Block_dev_base<Ds_data>,
00590   L4::Epiface_t<Block_dev<Ds_data>, L4virtio::Device>
00591 {
00592 private:
00593     class Irq_object : public L4::Irqep_t<Irq_object>
00594     {
00595     public:
00596         Irq_object(Block_dev<Ds_data> *parent) : _parent(parent) {}
00597
00598         void handle_irq()
00599         {
00600             _parent->kick();
00601         }
00602
00603     private:
00604         Block_dev<Ds_data> *_parent;
00605     };
00606     Irq_object _irq_handler;
00607
00608 protected:
00609     L4::Epiface *irq_iface()
00610     { return &_amp;_irq_handler; }
00611
00612 public:
00613     Block_dev(l4_uint32_t vendor, unsigned queue_size, l4_uint64_t capacity,
00614              bool read_only)
00615     : Block_dev_base<Ds_data>(vendor, queue_size, capacity, read_only),
00616       _irq_handler(this)
00617     {}
00618
00629     L4::Cap<void> register_obj(L4::Registry_iface *registry,
00630                               char const *service = 0)
00631     {
00632         L4Re::chkcap(registry->register_irq_obj(this->irq_iface()));
00633         L4::Cap<void> ret;
00634         if (service)
00635             ret = registry->register_obj(this, service);
00636         else
00637             ret = registry->register_obj(this);
00638         L4Re::chkcap(ret);
00639
00640         return ret;
00641     }
00642
00643     L4::Cap<void> register_obj(L4::Registry_iface *registry,
00644                               L4::Cap<L4::Rcv_endpoint> ep)
00645     {
00646         L4Re::chkcap(registry->register_irq_obj(this->irq_iface()));
00647
00648         return L4Re::chkcap(registry->register_obj(this, ep));
00649     }
00650
00651     typedef Block_request<Ds_data> Request;
00652     virtual bool process_request(cxx::unique_ptr<Request> &&req) = 0;
00653
00654 protected:

```



```

00669 L4::Ipc_svr::Server_iface *server_iface() const override
00670 {
00671     return this->L4::Epiface::server_iface();
00672 }
00673
00674 void kick()
00675 {
00676     for (;;)
00677     {
00678         auto req = this->get_request();
00679         if (!req)
00680             return;
00681         if (!this->process_request(cx::move(req)))
00682             return;
00683     }
00684 }
00685
00686 private:
00687 L4::Cap<L4::Irq> device_notify_irq() const override
00688 {
00689     return L4::cap_cast<L4::Irq>(_irq_handler.obj_cap());
00690 }
00691 };
00692
00693 } }

```

## 16.263 virtio-console

```

00001 // vi:ft=cpp
00002 /* SPDX-License-Identifier: MIT */
00003 /*
00004  * Copyright (C) 2019-2024 Kernkonzept GmbH.
00005  * Author(s): Sarah Hoffmann <sarah.hoffmann@kernkonzept.com>
00006  *           Phillip Raffeck <phillip.raffeck@kernkonzept.com>
00007  *           Steffen Liebergeld <steffen.liebergeld@kernkonzept.com>
00008  *           Jan Klötzke <jan.kloetzke@kernkonzept.com>
00009  */
00010 #pragma once
00011
00012 #include <l4/l4virtio/server/l4virtio>
00013 #include <l4/re/error_helper>
00014
00015 namespace L4virtio { namespace Svr { namespace Console {
00016
00017 struct Features : Dev_config::Features
00018 {
00019     Features() = default;
00020     explicit Features(l4_uint32_t raw) : Dev_config::Features(raw) {}
00021     CXX_BITFIELD_MEMBER(0, 0, console_size, raw);
00022     CXX_BITFIELD_MEMBER(1, 1, console_multiport, raw);
00023     CXX_BITFIELD_MEMBER(2, 2, emerg_write, raw);
00024 };
00025
00026 struct Control_message
00027 {
00028     enum Events
00029     {
00030         Device_ready = 0,
00031         Device_add = 1,
00032         Device_remove = 2,
00033         Port_ready = 3,
00034         Console_port = 4,
00035         Resize = 5,
00036         Port_open = 6,
00037         Port_name = 7,
00038     };
00039     l4_uint32_t id;
00040     l4_uint16_t event;
00041     l4_uint16_t value;
00042     Control_message() {}
00043     Control_message(l4_uint32_t i, l4_uint16_t e, l4_uint16_t v)
00044         : id(i), event(e), value(v) {}
00045 };
00046
00047 struct Control_request
00048 {
00049     Control_message *msg;
00050     l4_uint32_t len;
00051     Driver_mem_region *mem;
00052 };

```

```

00074
00109 struct Port
00110 {
00114     enum Port_status
00115     {
00117         Port_disabled = 0,
00119         Port_added,
00121         Port_ready,
00123         Port_open,
00125         Port_failed,
00127         Port_num_states,
00128     };
00129
00131     enum { Control_queue_size = 0x10 };
00132
00133     Virtqueue tx;
00134     Virtqueue rx;
00135     Port_status status;
00136     Port_status reported_status;
00137     unsigned vq_max;
00138
00139     Port() : status(Port_disabled), vq_max(Control_queue_size) {}
00140     Port(Port const &) = delete;
00141     Port &operator = (Port const &) = delete;
00142
00143     virtual ~Port() = default;
00144
00146     bool is_open() const
00147     { return status == Port_open; }
00148
00150     virtual void reset()
00151     {
00152         status = Port_disabled;
00153         reported_status = Port_disabled;
00154     }
00155
00157     bool queues_ready() const
00158     { return tx.ready() && rx.ready(); }
00159
00161     bool rx_ready() const
00162     { return is_open() && rx.ready(); }
00163
00165     bool tx_ready() const
00166     { return is_open() && tx.ready(); }
00167
00169     struct Transition {
00170         l4_int16_t event;
00171         l4_uint16_t value;
00172         Port_status next;
00173     };
00174
00194     static constexpr Transition
00195     state_transitions[Port_num_states][Port_num_states] =
00196     {
00197         /* reported          current          */
00198
00199         /* Port_disabled */ /* Port_disabled */ {{ -1, 0, Port_disabled },
00200             /* Port_added   */ { Control_message::Device_add, 0,
00201                 Port_added },
00202             /* Port_ready   */ { Control_message::Device_add, 0,
00203                 Port_ready },
00204             /* Port_open    */ { Control_message::Device_add, 0,
00205                 Port_ready },
00206             /* Port_failed   */ { Control_message::Device_add, 0,
00207                 Port_failed }},
00208
00209         /* Port_added      */ /* Port_disabled */ {{ Control_message::Device_remove,
00210             0, Port_disabled },
00211             /* Port_added   */ { -1, 0, Port_added },
00212             /* Port_ready   */ { -1, 0, Port_ready },
00213             /* Port_open    */ { Control_message::Port_open, 1,
00214                 Port_open },
00215             /* Port_failed   */ { -1, 0, Port_failed }},
00216
00217         /* Port_ready      */ /* Port_disabled */ {{ Control_message::Device_remove,
00218             0, Port_disabled },
00219             /* Port_added   */ { -1, 0, Port_added },
00220             /* Port_ready   */ { -1, 0, Port_ready },
00221             /* Port_open    */ { Control_message::Port_open, 1,
00222                 Port_open },
00223             /* Port_failed   */ { -1, 0, Port_failed }},
00224
00225         /* Port_open       */ /* Port_disabled */ {{ Control_message::Port_open, 0,
00226             Port_ready },
00227             /* Port_added   */ { Control_message::Port_open, 0,
00228                 Port_added },
00229             /* Port_ready   */ { Control_message::Port_open, 0,

```

```

00230                                     Port_ready },
00231                                     /* Port_open      */ { -1, 0, Port_open },
00232                                     /* Port_failed    */ { Control_message::Port_open, 0,
00233                                     Port_ready },},
00234
00235     /* Port_failed */ /* Port_disabled */ {{ Control_message::Device_remove,
00236     0, Port_disabled },},
00237     /* Port_added  */ { -1, 0, Port_added },
00238     /* Port_ready  */ { -1, 0, Port_ready },
00239     /* Port_open   */ { Control_message::Port_open, 1,
00240     Port_open },},
00241     /* Port_failed */ { -1, 0, Port_failed },},
00242 };
00243 };
00244
00267 class Virtio_con : public L4virtio::Svr::Device
00268 {
00269     enum Virtqueue_names
00270     {
00271         Ctrl_rx = 2,
00272         Ctrl_tx = 3,
00273     };
00274
00275     struct Serial_config_space
00276     {
00277         l4_uint16_t cols;
00278         l4_uint16_t rows;
00279         l4_uint32_t max_nr_ports;
00280         l4_uint32_t emerg_wr;
00281     } __attribute__((packed));
00282
00283 public:
00293     explicit Virtio_con(unsigned max_ports, bool enable_multiport)
00294     : L4virtio::Svr::Device(&_dev_config),
00295       _num_ports(enable_multiport ? max_ports : 1),
00296       _dev_config(L4VIRTIO_VENDOR_KK, L4VIRTIO_ID_CONSOLE,
00297         enable_multiport ? max_ports * 2 + 2 : 2)
00298     {
00299         if (_num_ports < 1)
00300             L4Re::chksys(-L4_EINVAL, "At least one port is required.");
00301
00302         Features hf(0);
00303
00304         hf.console_multiport() = enable_multiport;
00305
00306         _dev_config.host_features(0) = hf.raw;
00307
00308         if (enable_multiport)
00309             _dev_config.priv_config()->max_nr_ports = _num_ports;
00310         _dev_config.reset_hdr();
00311     }
00312
00313     void reset_queue_configs()
00314     {
00315         for (unsigned q = 0; q < _dev_config.num_queues(); ++q)
00316             reset_queue_config(q, max_queue_size(q));
00317     }
00318
00319     int reconfig_queue(unsigned index) override
00320     {
00321         if (index >= _dev_config.num_queues())
00322             return -L4_ERANGE;
00323
00324         if (setup_queue(get_queue(index), index, max_queue_size(index)))
00325             return 0;
00326
00327         return -L4_EINVAL;
00328     }
00329
00334     bool multiport_enabled() const
00335     {
00336         return _negotiated_features.console_multiport()
00337             && _dev_config.num_queues() > Ctrl_rx;
00338     }
00339
00340     bool ctrl_queue_ready() const
00341     { return _ctrl_port.is_open(); }
00342
00343     bool check_features(void) override
00344     {
00345         _negotiated_features = Features(_dev_config.negotiated_features(0));
00346         return true;
00347     }
00348
00349     bool check_queues() override
00350     {
00351         // NOTE

```

```

00352 // The VIRTIO specification states:
00353 // "The port 0 receive and transmit queues always exist"
00354 // The linux driver however does not setup port 0 if the multiport feature
00355 // is negotiated.
00356 // We just go along with the linux driver and do not expect port 0 to be up,
00357 // if the multiport feature is negotiated.
00358
00359 if (multiport_enabled())
00360     // If MULTIPORT was negotiated, ctrl queues should be set up.
00361     return _ctrl_port.queues_ready();
00362
00363 // If MULTIPORT was not negotiated, port 0 should be set up.
00364 port(0)->status = Port::Port_open;
00365 return port(0)->queues_ready();
00366 }
00367
00379 int port_add(unsigned idx)
00380 {
00381     Port *p = port(idx);
00382
00383     if (p->status != Port::Port_disabled)
00384         return -L4_EPERM;
00385
00386     p->status = Port::Port_added;
00387     port_report_status(idx);
00388
00389     return L4_EOK;
00390 }
00391
00403 int port_remove(unsigned idx)
00404 {
00405     Port *p = port(idx);
00406
00407     if (p->status == Port::Port_disabled)
00408         return -L4_EPERM;
00409
00410     p->status = Port::Port_disabled;
00411     port_report_status(idx);
00412
00413     return L4_EOK;
00414 }
00415
00428 int port_open(unsigned idx, bool open)
00429 {
00430     Port *p = port(idx);
00431
00432     if ((open && p->status != Port::Port_ready)
00433         || (!open && p->status != Port::Port_open))
00434         return -L4_EPERM;
00435
00436     p->status = open ? Port::Port_open : Port::Port_ready;
00437     port_report_status(idx);
00438
00439     return L4_EOK;
00440 }
00441
00455 int port_name(unsigned idx, char const *name)
00456 {
00457     Port *p = port(idx);
00458
00459     if (p->status == Port::Port_disabled)
00460         return -L4_EPERM;
00461
00462     return send_control_message(idx, Control_message::Port_name, 0, name);
00463 }
00464
00487 int send_control_message(l4_uint32_t idx, l4_uint16_t event,
00488                        l4_uint16_t value = 0, const char *name = 0)
00489 {
00490     if (!ctrl_queue_ready())
00491         return -L4_ENODEV;
00492
00493     Virtqueue *q = &_ctrl_port.rx;
00494     if (!q->ready())
00495         return -L4_ENODEV;
00496
00497     Virtqueue::Request r = q->next_avail();
00498     if (!r)
00499         return -L4_EBUSY;
00500
00501     Request_processor rp;
00502     Control_request req;
00503     rp.start(this, r, &req);
00504
00505     if (req.len < sizeof(Control_message))
00506         return -L4_ENOMEM;
00507

```

```

00508     Control_message msg(idx, event, value);
00509
00510     memcpy(req.msg, &msg, sizeof(msg));
00511
00512     if (event == Control_message::Port_name && name)
00513     {
00514         size_t name_len = cxx::min(req.len - sizeof(msg), strlen(name));
00515         memcpy(reinterpret_cast<char*>(req.msg) + sizeof(msg), name, name_len);
00516         q->finish(r, this, sizeof(msg) + name_len);
00517     }
00518     else
00519         q->finish(r, this, sizeof(msg));
00520
00521     return L4_EOK;
00522 }
00523
00536 int handle_control_message()
00537 {
00538     // Report port state transitions if that failed in the past...
00539     if (_report_port_state)
00540     {
00541         _report_port_state = false;
00542
00543         for (unsigned i = 0; i < _num_ports; ++i)
00544             if (!port_report_status(i))
00545                 _report_port_state = true;
00546     }
00547
00548     Virtqueue *q = &ctrl_port.tx;
00549     if (!q->ready())
00550         return -L4_ENODEV;
00551
00552     int ret = L4_EOK;
00553     Virtqueue::Request r;
00554     while ((r = q->next_avail()))
00555     {
00556         Request_processor rp;
00557         Control_request req;
00558
00559         rp.start(this, r, &req);
00560
00561         Control_message msg;
00562         if (req.len < sizeof(msg))
00563         {
00564             // Just ignore malformed input.
00565             q->finish(r, this);
00566             ret = -L4_EINVAL;
00567             continue;
00568         }
00569
00570         memcpy(&msg, req.msg, sizeof(msg));
00571         q->finish(r, this);
00572
00573         if (_ctrl_port.status == Port::Port_disabled)
00574         {
00575             // When the control queue is disabled, only device ready is accepted.
00576             if (msg.event == Control_message::Device_ready)
00577             {
00578                 if (msg.value)
00579                     _ctrl_port.status = Port::Port_open;
00580             }
00581
00582             process_device_ready(msg.value);
00583             continue;
00584         }
00585
00586         if (!ctrl_queue_ready())
00587             continue;
00588
00589         // Ignore invalid port ids
00590         if (msg.id >= max_ports())
00591             break;
00592
00593         switch (msg.event)
00594         {
00595             case Control_message::Port_ready:
00596                 process_port_ready(msg.id, msg.value);
00597                 break;
00598             case Control_message::Port_open:
00599                 process_port_open(msg.id, msg.value);
00600                 break;
00601             default:
00602                 ret = -L4_EINVAL;
00603                 break;
00604         }
00605     }
00606

```

```

00607     return ret;
00608 }
00609
00610 void load_desc(L4virtio::Virtqueue::Desc const &desc,
00611               Request_processor const *proc,
00612               L4virtio::Virtqueue::Desc const **table)
00613 {
00614     this->_mem_info.load_desc(desc, proc, table);
00615 }
00616
00617 void load_desc(L4virtio::Virtqueue::Desc const &desc,
00618               Request_processor const *proc,
00619               Control_request *data)
00620 {
00621     auto *region = this->_mem_info.find(desc.addr.get(), desc.len);
00622     if (L4_UNLIKELY(!region))
00623         throw Bad_descriptor(proc, Bad_descriptor::Bad_address);
00624     data->msg = reinterpret_cast<Control_message *>(region->local(desc.addr));
00625     data->len = desc.len;
00626     data->mem = region;
00627 }
00628
00629 void reset() override
00630 {
00631     for (unsigned p = 0; p < _num_ports; ++p)
00632         port(p)->reset();
00633
00634     _ctrl_port.reset();
00635     reset_queue_configs();
00636     _dev_config.reset_hdr();
00637     _negotiated_features = Features(0);
00638     _report_port_state = false;
00639
00640     reset_device();
00641 }
00642
00643 virtual void reset_device() {}
00644
00645 virtual void notify_queue(Virtqueue *queue) = 0;
00646
00647 virtual Port *port(unsigned port) = 0;
00648 virtual Port const *port(unsigned port) const = 0;
00649
00650 virtual void process_device_ready(l4_uint16_t value) = 0;
00651
00652 virtual void process_port_ready(l4_uint32_t id, l4_uint16_t value)
00653 {
00654     Port *p = port(id);
00655
00656     switch (p->status)
00657     {
00658     case Port::Port_added:
00659     case Port::Port_ready:
00660         p->status = value ? Port::Port_ready : Port::Port_failed;
00661         break;
00662     case Port::Port_open:
00663         if (!value)
00664             p->status = Port::Port_failed;
00665         break;
00666     default:
00667         // invalid state for PORT_READY message
00668         break;
00669     }
00670 }
00671
00672 virtual void process_port_open(l4_uint32_t id, l4_uint16_t value) = 0;
00673
00674 unsigned max_ports() const
00675 { return _num_ports; }
00676
00677 private:
00678 bool is_control_queue(unsigned q) const
00679 { return q == Ctrl_rx || q == Ctrl_tx; }
00680
00681 unsigned queue_to_port(unsigned q) const
00682 { return (q == 0 || q == 1) ? 0 : (q / 2) - 1; }
00683
00684 unsigned max_queue_size(unsigned q) const
00685 {
00686     if (is_control_queue(q))
00687         return _ctrl_port.vq_max;
00688
00689     return port(queue_to_port(q))->vq_max;
00690 }
00691
00692 Virtqueue *get_queue(unsigned q)

```

```

00765 {
00766     Port *p;
00767     if (is_control_queue(q))
00768         p = &_ctrl_port;
00769     else
00770         p = port(queue_to_port(q));
00771
00772     if (q & 1)
00773         return &p->tx;
00774     else
00775         return &p->rx;
00776 }
00777
00778 bool port_report_status(unsigned idx)
00779 {
00790     Port *p = port(idx);
00791     while (p->status != p->reported_status)
00792     {
00793         auto const &trans
00794             = Port::state_transitions[p->reported_status][p->status];
00795
00796         if (trans.event >= 0
00797             && send_control_message(idx, trans.event, trans.value) < 0)
00798         {
00799             _report_port_state = true;
00800             return false;
00801         }
00802
00803         p->reported_status = trans.next;
00804     }
00805
00806     return true;
00807 }
00808
00809 unsigned _num_ports;
00810 bool _report_port_state = false;
00811
00812 protected:
00813     Dev_config_t<Serial_config_space> _dev_config;
00814     Port _ctrl_port;
00815     Features _negotiated_features{0};
00816 };
00817
00818 }}} // name space

```

## 16.264 virtio-console-device

```

00001 // vi:ft=cpp
00002 /* SPDX-License-Identifier: MIT */
00003 /*
00004  * Copyright (C) 2019-2024 Kernkonzept GmbH.
00005  * Author(s): Sarah Hoffmann <sarah.hoffmann@kernkonzept.com>
00006  *            Phillip Raffeck <phillip.raffeck@kernkonzept.com>
00007  *            Steffen Liebergeld <steffen.liebergeld@kernkonzept.com>
00008  *            Jan Klötzke <jan.kloetzke@kernkonzept.com>
00009  */
00010 #pragma once
00011
00012 #include <l4/cxx/bitmap>
00013 #include <l4/cxx/static_vector>
00014 #include <l4/l4virtio/server/l4virtio>
00015 #include <l4/l4virtio/server/virtio-console>
00016 #include <l4/re/error_helper>
00017
00018 namespace L4virtio { namespace Svr { namespace Console {
00019
00026 struct Device_port : public Port
00027 {
00028     struct Buffer : Data_buffer
00029     {
00030         Buffer() = default;
00031         Buffer(Driver_mem_region const *r,
00032              Virtqueue::Desc const &d,
00033              Request_processor const *)
00034         {
00035             pos = static_cast<char *>(r->local(d.addr));
00036             left = d.len;
00037         }
00038     };
00039
00040     Request_processor rp;
00041     Virtqueue::Request request;
00042     Buffer src;

```

```

00043
00044     bool poll_in_req = true;
00045     bool poll_out_req = true;
00046
00047     void reset() override
00048     {
00049         Port::reset();
00050         request = Virtqueue::Request();
00051         poll_in_req = true;
00052         poll_out_req = true;
00053     }
00054 };
00055
00118 class Device
00119 : public Virtio_con
00120 {
00121     class Irq_object : public L4::Irqep_t<Irq_object>
00122     {
00123     public:
00124         Irq_object(Device *parent) : _parent(parent) {}
00125
00126         void handle_irq() { _parent->kick(); }
00127
00128     private:
00129         Device *_parent;
00130     };
00131
00132 protected:
00133     L4::Epiface *irq_iface()
00134     { return &_irq_handler; }
00135
00136 public:
00145     explicit Device(unsigned vq_max)
00146     : Virtio_con(1, false),
00147       _irq_handler(this),
00148       _ports(cxx::make_unique<Device_port[]>(1))
00149     {
00150         _ports[0].vq_max = vq_max;
00151         reset_queue_configs();
00152     }
00153
00163     explicit Device(unsigned vq_max, unsigned ports)
00164     : Virtio_con(ports, true),
00165       _irq_handler(this),
00166       _ports(cxx::make_unique<Device_port[]>(ports))
00167     {
00168         for (unsigned i = 0; i < ports; ++i)
00169             _ports[i].vq_max = vq_max;
00170         reset_queue_configs();
00171     }
00172
00182     explicit Device(cxx::static_vector<unsigned> const &vq_max_nums)
00183     : Virtio_con(vq_max_nums.size(), true),
00184       _irq_handler(this),
00185       _ports(cxx::make_unique<Device_port[]>(max_ports()))
00186     {
00187         for (unsigned i = 0; i < vq_max_nums.size(); ++i)
00188             _ports[i].vq_max = vq_max_nums[i];
00189         reset_queue_configs();
00190     }
00191
00192     void register_single_driver_irq() override
00193     {
00194         _kick_driver_irq = L4Re::Util::Unique_cap<L4::Irq>(
00195             L4Re::chkcapi(server_iface()->rcv_cap<L4::Irq>(0)));
00196         L4Re::chksys(server_iface()->realloc_rcv_cap(0));
00197     }
00198
00199     L4::Cap<L4::Irq> device_notify_irq() const override
00200     { return _irq_handler.obj_cap(); }
00201
00202     void notify_queue(Virtqueue *queue) override
00203     {
00204         if (queue->no_notify_guest())
00205             return;
00206
00207         _dev_config.add_irq_status(L4VIRTIO_IRQ_STATUS_VRING);
00208         _kick_driver_irq->trigger();
00209     }
00210
00214     virtual void rx_data_available(unsigned port) = 0;
00215
00219     virtual void tx_space_available(unsigned port) = 0;
00220
00224     virtual bool queues_stopped()
00225     { return false; }
00226

```



```

00227 void trigger_driver_config_irq() override
00228 {
00229     _dev_config.add_irq_status(L4VIRTIO_IRQ_STATUS_CONFIG);
00230     _kick_driver_irq->trigger();
00231 }
00232
00233 void kick()
00234 {
00235     if (queues_stopped())
00236         return;
00237
00238     // We're not interested in logging any errors, just ignore return value.
00239     handle_control_message();
00240
00241     for (unsigned i = 0; i < max_ports(); ++i)
00242     {
00243         auto &p = _ports[i];
00244         if (p.poll_in_req && p.tx_ready() && p.tx.desc_avail())
00245         {
00246             p.poll_in_req = false;
00247             rx_data_available(i);
00248         }
00249
00250         if (p.poll_out_req && p.rx_ready() && p.rx.desc_avail())
00251         {
00252             p.poll_out_req = false;
00253             tx_space_available(i);
00254         }
00255     }
00256 }
00257
00272 unsigned port_read(char *buf, unsigned len, unsigned port = 0)
00273 {
00274     unsigned total = 0;
00275     Device_port &p = _ports[port];
00276     Virtqueue *q = &p.tx;
00277
00278     Data_buffer dst;
00279     dst.pos = buf;
00280     dst.left = len;
00281
00282     while (dst.left)
00283     {
00284         try
00285         {
00286             // Make sure we have a valid request where we can read data from
00287             if (!p.request.valid())
00288             {
00289                 p.request = p.tx_ready() ? q->next_avail()
00290                     : Virtqueue::Request();
00291                 if (!p.request.valid())
00292                     break;
00293
00294                 p.rp.start(mem_info(), p.request, &p.src);
00295             }
00296
00297             total += p.src.copy_to(&dst);
00298
00299             // We might have eaten up the current descriptor. Move to the next
00300             // if this is the case. At the end of the descriptor chain we have
00301             // to retire the current request altogether.
00302             if (!p.src.left)
00303             {
00304                 if (!p.rp.next(mem_info(), &p.src))
00305                 {
00306                     q->finish(p.request, this);
00307                     p.request = Virtqueue::Request();
00308                 }
00309             }
00310         }
00311         catch (Bad_descriptor const &)
00312         {
00313             q->finish(p.request, this);
00314             p.request = Virtqueue::Request();
00315             device_error();
00316             break;
00317         }
00318     }
00319
00320     if (total < len)
00321         p.poll_in_req = true;
00322
00323     return total;
00324 }
00325
00341 unsigned port_write(char const *buf, unsigned len, unsigned port = 0)
00342 {

```

```

00343     unsigned total = 0;
00344     Device_port &p = _ports[port];
00345     Virtqueue *q = &p.rx;
00346
00347     Data_buffer src;
00348     src.pos = const_cast<char*>(buf);
00349     src.left = len;
00350
00351     Request_processor rp;
00352     while (src.left)
00353     {
00354         auto r = p.rx_ready() ? q->next_avail() : Virtqueue::Request();
00355         if (!r.valid())
00356             break;
00357
00358         l4_uint32_t chunk = 0;
00359         try
00360         {
00361             Device_port::Buffer dst;
00362             rp.start(mem_info(), r, &dst);
00363
00364             for (;;)
00365             {
00366                 chunk += src.copy_to(&dst);
00367                 if (!src.left)
00368                     break;
00369                 if (!rp.next(mem_info(), &dst))
00370                     break;
00371             }
00372         }
00373         catch (Bad_descriptor const &)
00374         {
00375             device_error();
00376         }
00377
00378         q->finish(r, this, chunk);
00379         total += chunk;
00380     }
00381
00382     if (total < len)
00383         p.poll_out_req = true;
00384
00385     return total;
00386 }
00387
00399 void process_device_ready(l4_uint16_t value) override
00400 {
00401     if (!value)
00402         return;
00403
00404     for (unsigned i = 0; i < max_ports(); ++i)
00405         port_add(i);
00406 }
00407
00422 void process_port_ready(l4_uint32_t id, l4_uint16_t value) override
00423 {
00424     Virtio_con::process_port_ready(id, value);
00425
00426     Port *p = port(id);
00427     if (p->status == Port::Port_failed)
00428         port_remove(id);
00429     else if (p->status == Port::Port_ready)
00430         port_open(id, true);
00431 }
00432
00443 void process_port_open(l4_uint32_t id, l4_uint16_t value) override
00444 {
00445     static_cast<void>(id);
00446     static_cast<void>(value);
00447 }
00448
00449 protected:
00450 Port* port(unsigned idx) override
00451 {
00452     return &_ports[idx];
00453 }
00454
00455 Port const *port(unsigned idx) const override
00456 {
00457     return &_ports[idx];
00458 }
00459
00460 private:
00461 Irq_object _irq_handler;
00462 cxx::unique_ptr<Device_port[]> _ports;
00463 L4Re::Util::Unique_cap<L4::Irq> _kick_driver_irq;
00464 };

```

```
00465
00466 }}} // name space
```

## 16.265 virtio-gpio-device

```
00001 // vi:set ft=c++: -- Mode: C++ --
00002 /*
00003  * Copyright (C) 2025 Kernkonzept GmbH.
00004  * Author(s): Christian Pöttsch <christian.poetzsch@kernkonzept.com>
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00008
00009 #pragma once
00010
00011 #include <l4/re/error_helper>
00012 #include <l4/sys/cxx/ipc_epiface>
00013
00014 #include <l4/l4virtio/server/virtio>
00015 #include <l4/l4virtio/server/l4virtio>
00016 #include <l4/l4virtio/l4virtio>
00017
00018 #include <l4/re/error_helper>
00019 #include <l4/re/util/object_registry>
00020 #include <l4/re/util/br_manager>
00021 #include <l4/sys/cxx/ipc_epiface>
00022 #include <l4/cxx/pair>
00023
00024 #include <vector>
00025 #include <memory>
00026
00027 namespace L4virtio {
00028 namespace Svr {
00029
00030 /* GPIO message status types */
00031 enum : l4_uint8_t
00032 {
00033     Gpio_status_ok = 0x0,
00034     Gpio_status_err = 0x1
00035 };
00036
00037 /* GPIO message types */
00038 enum : l4_uint8_t
00039 {
00040     Gpio_msg_get_line_names = 0x1,
00041     Gpio_msg_get_direction = 0x2,
00042     Gpio_msg_set_direction = 0x3,
00043     Gpio_msg_get_value = 0x4,
00044     Gpio_msg_set_value = 0x5,
00045     Gpio_msg_set_irq_type = 0x6
00046 };
00047
00048 /* GPIO value types */
00049 enum : l4_uint8_t
00050 {
00051     Gpio_low = 0x0,
00052     Gpio_high = 0x1
00053 };
00054
00055 /* GPIO direction types */
00056 enum : l4_uint8_t
00057 {
00058     Gpio_direction_none = 0x0,
00059     Gpio_direction_out = 0x1,
00060     Gpio_direction_in = 0x2
00061 };
00062
00063 /* GPIO interrupt types */
00064 enum : l4_uint8_t
00065 {
00066     Gpio_irq_type_none = 0x0,
00067     Gpio_irq_type_edge_rising = 0x1,
00068     Gpio_irq_type_edge_falling = 0x2,
00069     Gpio_irq_type_edge_both = 0x3,
00070     Gpio_irq_type_level_high = 0x4,
00071     Gpio_irq_type_level_low = 0x8
00072 };
00073
00074 /* GPIO interrupt status types */
00075 enum : l4_uint8_t
00076 {
00077     Gpio_irq_status_invalid = 0x0,
00078     Gpio_irq_status_valid = 0x1
```

```

00079 };
00080
00081 struct Gpio_request
00082 {
00083     14_uint16_t type;
00084     14_uint16_t gpio;
00085     14_uint32_t value;
00086 };
00087 static_assert(sizeof(Gpio_request) == 8,
00088     "Gpio_request contains padding bytes.");
00089
00090 struct Gpio_response
00091 {
00092     14_uint8_t status;
00093     14_uint8_t value;
00094 };
00095 static_assert(sizeof(Gpio_response) == 2,
00096     "Gpio_response contains padding bytes.");
00097
00098 struct Gpio_irq_request
00099 {
00100     14_uint16_t gpio;
00101 };
00102 static_assert(sizeof(Gpio_irq_request) == 2,
00103     "Gpio_irq_request contains padding bytes.");
00104
00105 struct Gpio_irq_response
00106 {
00107     14_uint8_t status;
00108 };
00109 static_assert(sizeof(Gpio_irq_response) == 1,
00110     "Gpio_irq_response contains padding bytes.");
00111
00112 struct Gpio_request_msg
00113 {
00114     struct Gpio_request *in_hdr = nullptr;
00115     struct Gpio_response *out_hdr = nullptr;
00116 };
00117
00118 struct Gpio_irq_request_msg
00119 {
00120     struct Gpio_irq_request *in_hdr = nullptr;
00121     struct Gpio_irq_response *out_hdr = nullptr;
00122 };
00123
00140 template <typename Request_handler,
00141     typename Epiface = L4virtio::Device>
00142 class Virtio_gpio : public L4virtio::Svr::Device,
00143     public L4::Epiface_t<Virtio_gpio<Request_handler,
00144         Epiface>,
00145         Epiface>
00146 {
00147 private:
00148     enum
00149     {
00150         queue_size = 128,
00151     };
00152
00153 public:
00154     using Gpio_request_handler = Request_handler;
00155
00166     struct Irq_handler
00167     {
00168         Irq_handler(Virtio_gpio *gpio, L4virtio::Svr::Virtqueue *q,
00169             L4virtio::Svr::Virtqueue::Head_desc const &head,
00170             14_uint8_t *status)
00171             : _gpio(gpio), _q(q), _head(head), _status(status)
00172         {}
00173
00174         void handle_irq()
00175         {
00176             *_status = Gpio_irq_status_valid;
00177             _q->finish(_head, _gpio, sizeof(Gpio_irq_response));
00178         }
00179
00180         void cancel()
00181         {
00182             *_status = Gpio_irq_status_invalid;
00183             _q->finish(_head, _gpio, sizeof(Gpio_irq_response));
00184         }
00185
00186 private:
00187     Virtio_gpio *_gpio;
00188     L4virtio::Svr::Virtqueue *_q;
00189     L4virtio::Svr::Virtqueue::Head_desc _head;
00190     14_uint8_t *_status;
00191 };

```

```

00192
00198 struct Host_irq : L4::Irqep_t<Host_irq>
00199 {
00200     explicit Host_irq(Virtio_gpio *gpio)
00201     : L4::Irqep_t<Host_irq>(), _gpio(gpio) {}
00202
00203     void handle_irq()
00204     { _gpio->handle_queue(); }
00205
00206 private:
00207     Virtio_gpio *_gpio;
00208 };
00209
00213 struct Request_processor : L4virtio::Svr::Request_processor
00214 {
00215     Request_processor(L4virtio::Svr::Virtqueue *q, Gpio_request_handler *hndlr,
00216                     Virtio_gpio *gpio)
00217     : _q(q), _req_handler(hndlr), _gpio(gpio), _head(), _req()
00218     {}
00219
00220 protected:
00221     bool init_queue()
00222     {
00223         auto r = _q->next_avail();
00224
00225         if (L4_UNLIKELY(!r))
00226             return false;
00227
00228         _head = start(_gpio->mem_info(), r, &_req);
00229
00230         return true;
00231     }
00232
00233 template <typename T>
00241 T get_request()
00242 {
00243     T req;
00244     req.in_hdr = reinterpret_cast<decltype(T::in_hdr)>(_req.pos);
00245
00246     // Need the next output buffer.
00247     if (!next(_gpio->mem_info(), &_req) || !current_flags().write())
00248         return req;
00249
00250     req.out_hdr = reinterpret_cast<decltype(T::out_hdr)>(_req.pos);
00251
00252     return req;
00253 }
00254
00255 struct Data_buffer : public L4virtio::Svr::Data_buffer
00256 {
00257     Data_buffer()
00258     {
00259         pos = nullptr;
00260         left = 0;
00261     }
00262     // This constructor is called from within start, so make it available.
00263     Data_buffer(L4virtio::Svr::Driver_mem_region const *r,
00264               L4virtio::Svr::Virtqueue::Desc const &d,
00265               L4virtio::Svr::Request_processor const *)
00266     {
00267         pos = static_cast<char *>(r->local(d.addr));
00268         left = d.len;
00269     }
00270
00271 };
00272
00273 L4virtio::Svr::Virtqueue *_q;
00274 Gpio_request_handler *_req_handler;
00275 Virtio_gpio *_gpio;
00276 L4virtio::Svr::Virtqueue::Head_desc _head;
00277 Data_buffer _req;
00278 };
00279
00280 // Handler for the gpio request queue
00281 struct Req_processor : Request_processor
00282 {
00283     using Request_processor::Request_processor;
00284
00285     void handle_request()
00286     {
00287         if (!this->_head)
00288             if (!this->init_queue())
00289                 return;
00290
00291         using Consumed_entry =
00292             cxx::Pair<L4virtio::Svr::Virtqueue::Head_desc, l4_uint32_t>;
00293         std::vector<Consumed_entry> consumed;

```

```

00294
00295     for (;;)
00296     {
00297         Gpio_request_msg req = this->template get_request<Gpio_request_msg>();
00298         if (!req.in_hdr || !req.out_hdr)
00299         {
00300             this->_gpio->device_error();
00301             break;
00302         }
00303
00304         // default response is error
00305         req.out_hdr->status = Gpio_status_err;
00306         switch (req.in_hdr->type)
00307         {
00308             case Gpio_msg_get_line_names:
00309                 // we don't support this
00310                 break;
00311             case Gpio_msg_get_direction:
00312             {
00313                 if (this->_req_handler->get_direction(req.in_hdr->gpio,
00314                                                     &req.out_hdr->value))
00315                     req.out_hdr->status = Gpio_status_ok;
00316                 break;
00317             }
00318             case Gpio_msg_set_direction:
00319             {
00320                 if (req.in_hdr->value == Gpio_direction_none ||
00321                     req.in_hdr->value == Gpio_direction_out ||
00322                     req.in_hdr->value == Gpio_direction_in)
00323                 {
00324                     if (this->_req_handler->set_direction(req.in_hdr->gpio,
00325                                                         req.in_hdr->value))
00326                         req.out_hdr->status = Gpio_status_ok;
00327                 }
00328                 break;
00329             }
00330             case Gpio_msg_get_value:
00331             {
00332                 if (this->_req_handler->get_value(req.in_hdr->gpio,
00333                                                  &req.out_hdr->value))
00334                     req.out_hdr->status = Gpio_status_ok;
00335                 break;
00336             }
00337             case Gpio_msg_set_value:
00338             {
00339                 if (req.in_hdr->value == Gpio_low ||
00340                     req.in_hdr->value == Gpio_high)
00341                 {
00342                     if (this->_req_handler->set_value(req.in_hdr->gpio,
00343                                                     req.in_hdr->value))
00344                         req.out_hdr->status = Gpio_status_ok;
00345                 }
00346                 break;
00347             }
00348             case Gpio_msg_set_irq_type:
00349             {
00350                 if (req.in_hdr->value == Gpio_irq_type_none ||
00351                     req.in_hdr->value == Gpio_irq_type_edge_rising ||
00352                     req.in_hdr->value == Gpio_irq_type_edge_falling ||
00353                     req.in_hdr->value == Gpio_irq_type_edge_both ||
00354                     req.in_hdr->value == Gpio_irq_type_level_high ||
00355                     req.in_hdr->value == Gpio_irq_type_level_low)
00356                 {
00357                     if (this->_req_handler->set_irq_type(req.in_hdr->gpio,
00358                                                         req.in_hdr->value))
00359                         req.out_hdr->status = Gpio_status_ok;
00360                 }
00361                 break;
00362             }
00363         }
00364
00365         // Save the descriptors which are done
00366         consumed.emplace_back(this->_head, sizeof(Gpio_response));
00367
00368         if (!this->init_queue())
00369             break;
00370     }
00371
00372     // Put all finished descriptors back into the used list and notify the
00373     // driver.
00374     this->_q->finish(consumed.begin(), consumed.end(), this->_gpio);
00375
00376     this->_head = Virtqueue::Head_desc();
00377 }
00378 };
00379
00380 // Handler for the gpio event queue

```

```

00381 struct Irq_req_processor : Request_processor
00382 {
00383     using Request_processor::Request_processor;
00384
00385     void handle_request()
00386     {
00387         if (!this->_head)
00388             if (!this->init_queue())
00389                 return;
00390
00391         for (;;)
00392         {
00393             // There is only one type of message in the event queue. This
00394             // basically arms (unmask) the irq.
00395             Gpio_irq_request_msg req = this->template get_request<Gpio_irq_request_msg>();
00396             if (!req.in_hdr || !req.out_hdr)
00397             {
00398                 this->_gpio->device_error();
00399                 break;
00400             }
00401
00402             // Save the virtio descriptor for this event in an extra Irq_handler
00403             // object. The descriptor will be returned to the client when the irq
00404             // is triggered or canceled.
00405             this->_req_handler->enable_irq(req.in_hdr->gpio,
00406                 std::make_shared<Irq_handler>(this->_gpio,
00407                     this->_q,
00408                     this->_head,
00409                     &req.out_hdr->status));
00410
00411             if (!this->init_queue())
00412                 break;
00413         }
00414
00415         this->_head = Virtqueue::Head_desc();
00416     }
00417 };
00418
00419 struct Features : public L4virtio::Svr::Dev_config::Features
00420 {
00421     Features() = default;
00422     Features(l4_uint32_t raw) : L4virtio::Svr::Dev_config::Features(raw) {}
00423
00424     CXX_BITFIELD_MEMBER(0, 0, gpio_f_irq, raw);
00425 };
00426
00427 struct Gpio_config_space
00428 {
00429     l4_uint16_t ngpio;
00430     l4_uint8_t padding[2];
00431     l4_uint32_t gpio_names_size;
00432 };
00433
00434 Virtio_gpio(Gpio_request_handler *hndlr,
00435             L4Re::Util::Object_registry *registry,
00436             l4_uint16_t ngpio)
00437 : L4virtio::Svr::Device(&_dev_config),
00438   _registry(registry),
00439   _dev_config(L4VIRTIO_VENDOR_KK, L4VIRTIO_ID_GPIO, 2),
00440   _host_irq(this),
00441   _req_processor(&_q[0], hndlr, this),
00442   _irq_req_processor(&_q[1], hndlr, this)
00443 {
00444     init_mem_info(2);
00445
00446     for (size_t i = 0; i < 2; i++)
00447     {
00448         reset_queue_config(i, queue_size);
00449         setup_queue(&_q[i], i, queue_size);
00450     }
00451
00452     registry->register_irq_obj(&_host_irq);
00453
00454     Features hf(0);
00455     hf.ring_indirect_desc() = true;
00456     hf.gpio_f_irq() = true;
00457     _dev_config.host_features(0) = hf.raw;
00458     _dev_config.set_host_feature(L4VIRTIO_FEATURE_VERSION_1);
00459
00460     // fill gpio config space
00461     _dev_config.priv_config()->ngpio = ngpio;
00462     _dev_config.priv_config()->gpio_names_size = 0; // not supported
00463
00464     _dev_config.reset_hdr();
00465 }
00466
00467 ~Virtio_gpio()

```

```

00468 { _registry->unregister_obj(&_host_irq); }
00469
00470 void notify_queue(L4virtio::Svr::Virtqueue *queue)
00471 {
00472     if (queue->no_notify_guest())
00473         return;
00474
00475     _dev_config.add_irq_status(L4VIRTIO_IRQ_STATUS_VRING);
00476     L4Re::chkipc(_notify_guest_irq->trigger(), "trigger guest irq");
00477 }
00478
00479 void handle_queue()
00480 {
00481     _req_processor.handle_request();
00482     _irq_req_processor.handle_request();
00483 }
00484
00485 void reset() override
00486 {}
00487
00488 bool check_queues() override
00489 { return true; }
00490
00491 int reconfig_queue(unsigned idx) override
00492 {
00493     if (idx >= sizeof(_q) / sizeof(_q[0]))
00494         return -L4_ERANGE;
00495
00496     return setup_queue(_q + idx, idx, queue_size);
00497 }
00498
00499 void trigger_driver_config_irq() override
00500 {
00501     _dev_config.add_irq_status(L4VIRTIO_IRQ_STATUS_CONFIG);
00502     _notify_guest_irq->trigger();
00503 }
00504
00505 L4::Ipc_svr::Server_iface *server_iface() const override
00506 { return L4::Epiface::server_iface(); }
00507
00508 long op_set_status(L4virtio::Device::Rights r, unsigned status)
00509 { return L4virtio::Svr::Device::op_set_status(r, status); }
00510
00511 long op_config_queue(L4virtio::Device::Rights r, unsigned queue)
00512 { return L4virtio::Svr::Device::op_config_queue(r, queue); }
00513
00514 long op_device_config(L4virtio::Device::Rights r,
00515                       L4::Ipc::Cap<L4Re::Dataspace> &config_ds,
00516                       L4_addr_t &ds_offset)
00517 { return L4virtio::Svr::Device::op_device_config(r, config_ds, ds_offset); }
00518
00519 L4::Cap<L4::Irc> device_notify_irq() const override
00520 { return L4::cap_cast<L4::Irc>(_host_irq.obj_cap()); }
00521
00522 void register_single_driver_irq() override
00523 {
00524     _notify_guest_irq = L4Re::chkcapi
00525         (server_iface()->template rcv_cap<L4::Irc>(0));
00526
00527     L4Re::chksys(server_iface()->realloc_rcv_cap(0));
00528 }
00529
00530 private:
00531     L4Re::Util::Object_registry *_registry;
00532     L4virtio::Svr::Dev_config_t<Gpio_config_space> _dev_config;
00533     Host_irq _host_irq;
00534     L4::Cap<L4::Irc> _notify_guest_irq;
00535     L4virtio::Svr::Virtqueue _q[2];
00536     Req_processor _req_processor;
00537     Irq_req_processor _irq_req_processor;
00538 };
00539
00540 } // namespace Svr
00541 } // namespace L4virtio

```

## 16.266 virtio-i2c-device

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00002 /*
00003  * Copyright (C) 2024-2025 Kernkonzept GmbH.
00004  * Author(s): Martin Kuetzler <martin.kuetzler@kernkonzept.com>
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)

```



```

00007  */
00008
00009 #pragma once
00010
00011 #include <l4/re/error_helper>
00012 #include <l4/sys/cxx/ipc_epiface>
00013
00014 #include <l4/l4virtio/server/virtio>
00015 #include <l4/l4virtio/server/l4virtio>
00016 #include <l4/l4virtio/l4virtio>
00017
00018 #include <l4/re/error_helper>
00019 #include <l4/re/util/object_registry>
00020 #include <l4/re/util/br_manager>
00021 #include <l4/sys/cxx/ipc_epiface>
00022
00023 #include <vector>
00024 #include <l4/cxx/pair>
00025
00026 namespace L4virtio {
00027 namespace Svr {
00028
00029 enum : l4_uint8_t
00030 {
00031     I2c_msg_ok = 0,
00032     I2c_msg_err = 1,
00033 };
00034
00035 struct I2c_request_flags
00036 {
00037     l4_uint32_t raw;
00038
00039     CXX_BITFIELD_MEMBER(0, 0, fail_next, raw);
00040     CXX_BITFIELD_MEMBER(1, 1, m_rd, raw);
00041 };
00042 static_assert(sizeof(I2c_request_flags) == 4,
00043     "I2c_request_flags contains padding bytes.");
00044
00045 struct I2c_out_hdr
00046 {
00047     l4_uint16_t addr;
00048     l4_uint16_t padding;
00049     I2c_request_flags flags;
00050 };
00051 static_assert(sizeof(I2c_out_hdr) == 8, "I2c_out_hdr contains padding bytes.");
00052
00053 struct I2c_in_hdr
00054 {
00055     l4_uint8_t status;
00056 };
00057 static_assert(sizeof(I2c_in_hdr) == 1, "I2c_in_hdr contains padding bytes.");
00058
00059 struct I2c_req
00060 {
00061     struct I2c_out_hdr out_hdr;
00062     unsigned buf_len;
00063     l4_uint8_t* buf;
00064     struct I2c_in_hdr *in_hdr;
00065
00066     unsigned write_size;
00067
00068     void set_status(l4_uint8_t status)
00069     {
00070         in_hdr->status = status;
00071     }
00072 };
00073
00084 template <typename Request_handler,
00085     typename Epiface = L4virtio::Device>
00086 class Virtio_i2c : public L4virtio::Svr::Device,
00087     public L4::Epiface_t<Request_handler,
00088         Epiface>,
00089     Epiface>
00090 {
00091 private:
00092     enum
00093     {
00094         Num_request_queues = 1,
00095         queue_size = 128,
00096     };
00097
00098 public:
00099     using I2c_request_handler = Request_handler;
00100
00106     class Host_irq : public L4::Irqep_t<Host_irq>
00107     {
00108     public:

```

```

00109     explicit Host_irq(Virtio_i2c *i2c) : L4::Irqep_t<Host_irq>(), _i2c(i2c) {}
00110
00111     void handle_irq()
00112     {
00113         _i2c->handle_queue();
00114     }
00115
00116 private:
00117     Virtio_i2c *_i2c;
00118 };
00119
00123 class Request_processor : public L4virtio::Svr::Request_processor
00124 {
00125 public:
00126
00127     struct Data_buffer : public L4virtio::Svr::Data_buffer
00128     {
00129         Data_buffer()
00130         {
00131             pos = nullptr;
00132             left = 0;
00133         }
00134         // This constructor is called from within start, so make it available.
00135         Data_buffer(L4virtio::Svr::Driver_mem_region const *r,
00136                     L4virtio::Svr::Virtqueue::Desc const &d,
00137                     L4virtio::Svr::Request_processor const *)
00138         {
00139             pos = static_cast<char *>(r->local(d.addr));
00140             left = d.len;
00141         }
00142     };
00143
00144     Request_processor(L4virtio::Svr::Virtqueue *q, I2c_request_handler *hndlr,
00145                      Virtio_i2c *i2c)
00146         : _q(q), _req_handler(hndlr), _i2c(i2c), _head(), _req(),
00147           _fail_next(false)
00148     {}
00149
00150     bool init_queue()
00151     {
00152         auto r = _q->next_avail();
00153         if (L4_UNLIKELY(!r))
00154             return false;
00155
00156         _head = start(_i2c->mem_info(), r, &_req);
00157
00158         return true;
00159     }
00160
00161     I2c_req get_request()
00162     {
00163         I2c_req request;
00164         memcpy(&request.out_hdr, _req.pos, sizeof(I2c_out_hdr));
00165
00166         // number of bytes to be written in the answer.
00167         request.write_size = sizeof(I2c_in_hdr);
00168         request.buf_len = 0;
00169
00170         Data_buffer req;
00171         // 2nd part: either the optional buffer or the in_hdr
00172         if (next(_i2c->mem_info(), &req))
00173         {
00174             request.buf_len += req.left;
00175             request.buf = reinterpret_cast<l4_uint8_t *>(req.pos);
00176         }
00177
00178         // 3rd part: in_hdr
00179         if (next(_i2c->mem_info(), &req))
00180         {
00181             // 2nd part was indeed a buffer
00182             if (request.out_hdr.flags.m_rd())
00183                 request.write_size += request.buf_len;
00184
00185             // actual 3rd part
00186             request.in_hdr = reinterpret_cast<I2c_in_hdr *>(req.pos);
00187         }
00188         else
00189         {
00190             // no 3rd part, 2nd part is in_hdr;
00191             request.in_hdr = reinterpret_cast<I2c_in_hdr *>(request.buf);
00192             request.buf = nullptr;
00193             request.buf_len = 0;
00194         }
00195     }
00196
00197     // no 3rd part, 2nd part is in_hdr;
00198     request.in_hdr = reinterpret_cast<I2c_in_hdr *>(request.buf);
00199     request.buf = nullptr;
00200     request.buf_len = 0;
00201 }
00202
00203
00204
00205
00206
00207

```

```

00208     return request;
00209 }
00210
00211 void handle_request()
00212 {
00213     if (!_head)
00214         if (!init_queue())
00215             return;
00216
00217     using Consumed_entry =
00218         cxx::Pair<L4virtio::Svr::Virtqueue::Head_desc, l4_uint32_t>;
00219     std::vector<Consumed_entry> consumed;
00220
00221     for (;;)
00222     {
00223         auto r = get_request();
00224         if (_fail_next)
00225         {
00226             r.set_status(I2c_msg_err);
00227             _fail_next = r.out_hdr.flags.fail_next();
00228         }
00229         else
00230         {
00231             bool ok;
00232             l4_uint16_t i2c_addr = r.out_hdr.addr >> 1;
00233             if (r.out_hdr.flags.m_rd())
00234                 ok = _req_handler->handle_read(i2c_addr, r.buf, r.buf_len);
00235             else
00236                 ok = _req_handler->handle_write(i2c_addr, r.buf, r.buf_len);
00237             if (ok)
00238             {
00239                 r.set_status(I2c_msg_ok);
00240                 _fail_next = false;
00241             }
00242             else
00243             {
00244                 r.set_status(I2c_msg_err);
00245                 _fail_next = r.out_hdr.flags.fail_next();
00246             }
00247         }
00248         consumed.emplace_back(_head, r.write_size);
00249         if (!init_queue())
00250             break;
00251     }
00252
00253     _q->finish(consumed.begin(), consumed.end(), _i2c);
00254
00255     _head = Virtqueue::Head_desc();
00256 }
00257
00258 private:
00259     L4virtio::Svr::Virtqueue *_q;
00260     I2c_request_handler *_req_handler;
00261     Virtio_i2c *_i2c;
00262     L4virtio::Svr::Virtqueue::Head_desc _head;
00263     Data_buffer _req;
00264     bool _fail_next;
00265 };
00266
00267 struct Features : public L4virtio::Svr::Dev_config::Features
00268 {
00269     Features() = default;
00270     Features(l4_uint32_t raw) : L4virtio::Svr::Dev_config::Features(raw) {}
00271
00272     // This feature is mandatory. The driver is requested to abort communication
00273     // if this is not offered.
00274     CXX_BITFIELD_MEMBER(0, 0, zero_length_request, raw);
00275 };
00276
00277 Virtio_i2c(I2c_request_handler *hndlr, L4Re::Util::Object_registry *registry)
00278 : L4virtio::Svr::Device(&_dev_config),
00279   _dev_config(L4VIRTIO_VENDOR_KK, L4VIRTIO_ID_I2C, Num_request_queues),
00280   _req_handler(hndlr),
00281   _host_irq(this),
00282   _request_processor(&_q, hndlr, this)
00283 {
00284     init_mem_info(2);
00285     reset_queue_config(0, queue_size);
00286     setup_queue(&_q, 0, queue_size);
00287     registry->register_irq_obj(&_host_irq);
00288
00289     Features hf(0);
00290     hf.ring_indirect_desc() = true;
00291     hf.zero_length_request() = true;
00292     _dev_config.host_features(0) = hf.raw;
00293     _dev_config.set_host_feature(L4VIRTIO_FEATURE_VERSION_1);
00294     _dev_config.reset_hdr();

```

```

00295     }
00296
00297 void notify_queue(L4virtio::Svr::Virtqueue *)
00298 {
00299     if (_q.no_notify_guest())
00300         return;
00301
00302     _dev_config.add_irq_status(L4VIRTIO_IRQ_STATUS_VRING);
00303     L4Re::chkipc(_notify_guest_irq->trigger(), "trigger guest irq");
00304 }
00305
00306 void handle_queue()
00307 {
00308     _request_processor.handle_request();
00309 }
00310
00311 void reset() override
00312 {
00313 }
00314
00315 bool check_queues() override
00316 {
00317     return true;
00318 }
00319
00320 int reconfig_queue(unsigned idx) override
00321 {
00322     if (idx != 0)
00323         return -L4_ERANGE;
00324
00325     setup_queue(&_q, 0, queue_size);
00326
00327     return L4_EOK;
00328 }
00329
00330 void trigger_driver_config_irq() override
00331 {
00332     _dev_config.add_irq_status(L4VIRTIO_IRQ_STATUS_CONFIG);
00333     _notify_guest_irq->trigger();
00334 }
00335
00336 L4::Ipc_svr::Server_iface *server_iface() const override
00337 {
00338     return L4::Epiface::server_iface();
00339 }
00340
00341 long op_set_status(L4virtio::Device::Rights r, unsigned status)
00342 {
00343     return L4virtio::Svr::Device::op_set_status(r, status);
00344 }
00345
00346 long op_config_queue(L4virtio::Device::Rights r, unsigned queue)
00347 {
00348     return L4virtio::Svr::Device::op_config_queue(r, queue);
00349 }
00350
00351 long op_device_config(L4virtio::Device::Rights r,
00352                      L4::Ipc::Cap<L4Re::Dataspace> &config_ds,
00353                      L4_addr_t &ds_offset)
00354 {
00355     return L4virtio::Svr::Device::op_device_config(r, config_ds, ds_offset);
00356 }
00357
00358 L4::Cap<L4::Irq> device_notify_irq() const override
00359 {
00360     return L4::cap_cast<L4::Irq>(_host_irq.obj_cap());
00361 }
00362
00363 void register_single_driver_irq() override
00364 {
00365     _notify_guest_irq = L4Re::chkcapi
00366         (server_iface()->template rcv_cap<L4::Irq>(0));
00367
00368     L4Re::chksys(server_iface()->realloc_rcv_cap(0));
00369 }
00370
00371
00372 private:
00373     L4virtio::Svr::Dev_config_t<L4virtio::Svr::No_custom_data> _dev_config;
00374     I2c_request_handler *_req_handler;
00375     L4virtio::Svr::Virtqueue _q;
00376     Host_irq _host_irq;
00377     L4::Cap<L4::Irq> _notify_guest_irq;
00378     Request_processor _request_processor;
00379 };
00380
00381 } // namespace Svr

```

```
00382 } // namespace L4virtio
```

## 16.267 virtio-rng-device

```
00001 // vi:ft=cpp: -*- Mode: C++ -*-
00002 /*
00003  * Copyright (C) 2024-2025 Kernkonzept GmbH.
00004  * Author(s): Martin Kuettler <martin.kuettler@kernkonzept.com>
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00008
00009 #pragma once
00010
00011 #include <l4/re/error_helper>
00012 #include <l4/sys/cxx/ipc_epiface>
00013
00014 #include <l4/l4virtio/server/virtio>
00015 #include <l4/l4virtio/server/l4virtio>
00016 #include <l4/l4virtio/l4virtio>
00017
00018 namespace L4virtio {
00019 namespace Svr {
00020
00021     template <typename Rnd_state, typename Epiface = L4virtio::Device>
00022     class Virtio_rng : public L4virtio::Svr::Device,
00023                       public L4::Epiface_t<Virtio_rng<Rnd_state>, Epiface>
00024     {
00025     private:
00026         enum
00027         {
00028             Num_request_queues = 1,
00029             queue_size = 128,
00030         };
00031     public:
00032         using Random_state = Rnd_state;
00033
00034         class Host_irq : public L4::Irqep_t<Host_irq>
00035         {
00036         public:
00037             explicit Host_irq(Virtio_rng *rng) : L4::Irqep_t<Host_irq>(), _rng(rng) {}
00038
00039             void handle_irq()
00040             {
00041                 _rng->handle_queue();
00042             }
00043         private:
00044             Virtio_rng *_rng;
00045         };
00046
00047         class Request_processor : public L4virtio::Svr::Request_processor
00048         {
00049         public:
00050             struct Data_buffer : public L4virtio::Svr::Data_buffer
00051             {
00052                 Data_buffer() = default;
00053                 // This constructor is called from within start, so make it available.
00054                 Data_buffer(L4virtio::Svr::Driver_mem_region const *r,
00055                             L4virtio::Svr::Virtqueue::Desc const &d,
00056                             L4virtio::Svr::Request_processor const *)
00057                 {
00058                     pos = static_cast<char *>(r->local(d.addr));
00059                     left = d.len;
00060                 }
00061             };
00062
00063             Request_processor(L4virtio::Svr::Virtqueue *q, Random_state *rnd,
00064                               Virtio_rng *rng)
00065                 : _q(q), _rnd(rnd), _rng(rng), _head() {}
00066
00067             bool init_queue()
00068             {
00069                 auto r = _q->next_avail();
00070
00071                 if (L4_UNLIKELY(!r))
00072                     return false;
00073
00074                 _head = start(_rng->mem_info(), r, &_req);
00075
00076                 return true;
00077             }
00078         };
00079     };
00080 }
```

```

00099
00100 void handle_request()
00101 {
00102     if (!_head)
00103         if (!init_queue())
00104             return;
00105
00106     for (;;)
00107     {
00108         auto const pos = reinterpret_cast<unsigned char *>(_req.pos);
00109         L4Re::chksys(_rnd->get_random(_req.left, pos), "get random");
00110         _q->finish(_head, _rng, _req.left);
00111         if (!init_queue())
00112             break;
00113     }
00114     return;
00115 }
00116
00117 private:
00118     L4virtio::Svr::Virtqueue *_q;
00119     Random_state *_rnd;
00120     Virtio_rng *_rng;
00121     L4virtio::Svr::Virtqueue::Head_desc _head;
00122     Data_buffer _req;
00123 };
00124
00125 Virtio_rng(Random_state *rnd, L4::Registry_iface *registry)
00126 : L4virtio::Svr::Device(&_dev_config),
00127   _dev_config(L4VIRTIO_VENDOR_KK, L4VIRTIO_ID_RNG, Num_request_queues),
00128   _rnd(rnd),
00129   _host_irq(this),
00130   _request_processor(&_q, rnd, this)
00131 {
00132     init_mem_info(2);
00133     reset_queue_config(0, queue_size);
00134     setup_queue(&_q, 0, queue_size);
00135     registry->register_irq_obj(&_host_irq);
00136
00137     L4virtio::Svr::Dev_config::Features hf;
00138     hf.ring_indirect_desc() = true;
00139     _dev_config.host_features(0) = hf.raw;
00140     _dev_config.set_host_feature(L4VIRTIO_FEATURE_VERSION_1);
00141     _dev_config.reset_hdr();
00142 }
00143
00144 void notify_queue(L4virtio::Svr::Virtqueue *)
00145 {
00146     if (_q.no_notify_guest())
00147         return;
00148
00149     _dev_config.add_irq_status(L4VIRTIO_IRQ_STATUS_VRING);
00150     L4Re::chkipc(_notify_guest_irq->trigger(), "trigger guest irq");
00151 }
00152
00153 void handle_queue()
00154 {
00155     _request_processor.handle_request();
00156 }
00157
00158 void reset() override
00159 {
00160 }
00161
00162 bool check_queues() override
00163 {
00164     return true;
00165 }
00166
00167 int reconfig_queue(unsigned idx) override
00168 {
00169     if (idx != 0)
00170         return -L4_ERANGE;
00171
00172     setup_queue(&_q, 0, queue_size);
00173
00174     return L4_EOK;
00175 }
00176
00177 void trigger_driver_config_irq() override
00178 {
00179     _dev_config.add_irq_status(L4VIRTIO_IRQ_STATUS_CONFIG);
00180     _notify_guest_irq->trigger();
00181 }
00182
00183 L4::Ipc_svr::Server_iface *server_iface() const override
00184 {
00185     return L4::Epiface::server_iface();

```

```

00186     }
00187
00188     long op_set_status(L4virtio::Device::Rights r, unsigned status)
00189     {
00190         return L4virtio::Svr::Device::op_set_status(r, status);
00191     }
00192
00193     long op_config_queue(L4virtio::Device::Rights r, unsigned queue)
00194     {
00195         return L4virtio::Svr::Device::op_config_queue(r, queue);
00196     }
00197
00198     long op_device_config(L4virtio::Device::Rights r,
00199                          L4::Ipc::Cap<L4Re::Dataspace> &config_ds,
00200                          l4_addr_t &ds_offset)
00201     {
00202         return L4virtio::Svr::Device::op_device_config(r, config_ds, ds_offset);
00203     }
00204
00205     L4::Cap<L4::Irq> device_notify_irq() const override
00206     {
00207         return L4::cap_cast<L4::Irq>(_host_irq.obj_cap());
00208     }
00209
00210     void register_single_driver_irq() override
00211     {
00212         _notify_guest_irq = L4Re::chkcap
00213             (server_iface()->template rcv_cap<L4::Irq>(0));
00214
00215         L4Re::chksys(server_iface()->realloc_rcv_cap(0));
00216     }
00217
00218 private:
00219     L4virtio::Svr::Dev_config_t<L4virtio::Svr::No_custom_data>_dev_config;
00220     Random_state *_rnd;
00221     L4virtio::Svr::Virtqueue _q;
00222     Host_irq _host_irq;
00223     L4::Cap<L4::Irq> _notify_guest_irq;
00224     Request_processor _request_processor;
00225 };
00226
00227
00228 } // namespace Svr
00229 } // namespace L4virtio

```

## 16.268 virtio-scmi-device

```

00001 // vi:ft=cpp
00002 /* SPDX-License-Identifier: MIT */
00003 /*
00004  * Copyright (C) 2024 Kernkonzept GmbH.
00005  * Author(s): Christian Pöttsch <christian.poetzsch@kernkonzept.com>
00006  *
00007  * License: see LICENSE.spdx (in this directory or the directories above)
00008  */
00009 #pragma once
00010
00011 #include <l4/cxx/bitmap>
00012 #include <l4/l4virtio/l4virtio>
00013 #include <l4/l4virtio/server/l4virtio>
00014 #include <l4/l4virtio/server/virtio>
00015 #include <l4/re/util/object_registry>
00016
00017 #include <map>
00018 #include <vector>
00019
00020 namespace L4virtio { namespace Svr { namespace Scmi {
00021
00022     enum
00023     {
00024         Version = 0x20000
00025     };
00026
00027     enum
00028     {
00029         Success = 0,
00030         Not_supported = -1,
00031         Invalid_parameters = -2,
00032         Denied = -3,
00033         Not_found = -4,
00034         Out_of_range = -5,
00035         Busy = -6,
00036         Comms_error = -7,

```

```

00039     Generic_error = -8,
00040     Hardware_error = -9,
00041     Protocol_error = -10
00042 };
00043
00045 struct Scmi_hdr_t
00046 {
00047     14_uint32_t hdr_raw = 0;
00048     CXX_BITFIELD_MEMBER(18, 27, token, hdr_raw);
00049     CXX_BITFIELD_MEMBER(10, 17, protocol_id, hdr_raw);
00050     CXX_BITFIELD_MEMBER( 8,  9, message_type, hdr_raw);
00051     CXX_BITFIELD_MEMBER( 0,  7, message_id, hdr_raw);
00052 };
00053
00055 enum
00056 {
00057     Base_protocol = 0x10,
00058     Power_domain_management_protocol = 0x11,
00059     System_power_management_protocol = 0x12,
00060     Performance_domain_management_protocol = 0x13,
00061     Clock_management_protocol = 0x14,
00062     Sensor_management_protocol = 0x15,
00063     Reset_domain_management_protocol = 0x16,
00064     Voltage_domain_management_protocol = 0x17
00065 };
00066
00068 enum
00069 {
00070     Protocol_version = 0x0,
00071     Protocol_attributes = 0x1,
00072     Protocol_message_attributes = 0x2,
00073 };
00074
00076 enum
00077 {
00078     Base_discover_vendor = 0x3,
00079     Base_discover_sub_vendor = 0x4,
00080     Base_discover_implementation_version = 0x5,
00081     Base_discover_list_protocols = 0x6,
00082     Base_discover_agent = 0x7,
00083     Base_notify_errors = 0x8,
00084     Base_set_device_permissions = 0x9,
00085     Base_set_protocol_permissions = 0xa,
00086     Base_reset_agent_configuration = 0xb
00087 };
00088
00090 struct Base_attr_t
00091 {
00092     14_uint32_t attr_raw = 0;
00093     CXX_BITFIELD_MEMBER(8, 15, nagents, attr_raw);
00094     CXX_BITFIELD_MEMBER(0,  7, nprots, attr_raw);
00095 };
00096
00098 enum
00099 {
00100     Performance_domain_attributes = 0x3,
00101     Performance_describe_levels = 0x4,
00102     Performance_limits_set = 0x5,
00103     Performance_limits_get = 0x6,
00104     Performance_level_set = 0x7,
00105     Performance_level_get = 0x8,
00106     Performance_notify_limits = 0x9,
00107     Performance_notify_level = 0xa,
00108     Performance_describe_fastchannel = 0xb,
00109 };
00110
00112 struct Performance_attr_t
00113 {
00114     14_uint32_t attr_raw = 0;
00115     CXX_BITFIELD_MEMBER(16, 16, power, attr_raw);
00116     CXX_BITFIELD_MEMBER( 0, 15, domains, attr_raw);
00117
00118     14_uint32_t stat_addr_low = 0;
00119     14_uint32_t stat_addr_high = 0;
00120     14_uint32_t stat_len = 0;
00121 };
00122
00124 struct Performance_domain_attr_t
00125 {
00126     14_uint32_t attr_raw = 0;
00127     CXX_BITFIELD_MEMBER(31, 31, set_limits, attr_raw);
00128     CXX_BITFIELD_MEMBER(30, 30, set_perf_level, attr_raw);
00129     CXX_BITFIELD_MEMBER(29, 29, perf_limits_change_notify, attr_raw);
00130     CXX_BITFIELD_MEMBER(28, 28, perf_level_change_notify, attr_raw);
00131     CXX_BITFIELD_MEMBER(27, 27, fast_channel, attr_raw);
00132
00133     14_uint32_t rate_limit_raw = 0;

```



```

00134 CXX_BITFIELD_MEMBER( 0, 19, rate_limit, rate_limit_raw);
00135
00136 l4_uint32_t sustained_freq = 0;
00137 l4_uint32_t sustained_perf_level = 0;
00138 char name[16] = { 0 };
00139 };
00140
00142 struct Performance_describe_levels_n_t
00143 {
00144     l4_uint32_t num_levels_raw = 0;
00145     CXX_BITFIELD_MEMBER(16, 31, nremain_perf_levels, num_levels_raw);
00146     CXX_BITFIELD_MEMBER( 0, 11, nperf_levels, num_levels_raw);
00147 };
00148
00150 struct Performance_describe_level_t
00151 {
00152     l4_uint32_t perf_level = 0;
00153     l4_uint32_t power_cost = 0;
00154     l4_uint16_t trans_latency = 0;
00155     l4_uint16_t res0 = 0;
00156 };
00157
00158 template<typename OBSERV>
00159 struct Queue_worker : Request_processor
00160 {
00161     Queue_worker(OBSERV *o, Virtqueue *queue)
00162     : o(o), q(queue)
00163     {}
00164
00165     bool init_queue()
00166     {
00167         auto r = q->next_avail();
00168
00169         if (L4_UNLIKELY(!r))
00170             return false;
00171
00172         head = start(o->mem_info(), r, &req);
00173
00174         return true;
00175     }
00176
00177     bool next()
00178     { return Request_processor::next(o->mem_info(), &req); }
00179
00180     void finish(l4_uint32_t total)
00181     { q->finish(head, o, total); }
00182
00183     template<typename T>
00184     l4_ssize_t read(Data_buffer *buf, T *data, l4_size_t s = sizeof(T))
00185     {
00186         buf->pos = reinterpret_cast<char *>(data);
00187         buf->left = s;
00188         l4_size_t chunk = 0;
00189         for (;;)
00190         {
00191             chunk += req.copy_to(buf);
00192             if (req.done())
00193                 next();
00194             if (!buf->left)
00195                 break;
00196         }
00197         if (chunk != s)
00198             return -1;
00199         return chunk;
00200     }
00201
00202     template<typename T>
00203     l4_ssize_t write(Data_buffer *buf, T *data, l4_size_t s = sizeof(T))
00204     {
00205         buf->pos = reinterpret_cast<char *>(data);
00206         buf->left = s;
00207         l4_size_t chunk = 0;
00208         for (;;)
00209         {
00210             chunk += buf->copy_to(&req);
00211             if (req.done())
00212                 next();
00213             if (!buf->left)
00214                 break;
00215         }
00216         if (chunk != s)
00217             return -1;
00218         return chunk;
00219     }
00220
00221     l4_ssize_t handle_request()
00222     {

```



```

00348     void handle_irq() { c->kick(); }
00349 };
00350
00351 enum
00352 {
00353     Queue_size = 0x10
00354 };
00355
00356 public:
00357     Scmi_dev(L4Re::Util::Object_registry *registry)
00358     : L4virtio::Svr::Device(&_dev_config),
00359       _dev_config(L4VIRTIO_VENDOR_KK, L4VIRTIO_ID_SCMI, 1),
00360       _host_irq(this),
00361       _request_worker(this, &_q[0])
00362     {
00363         init_mem_info(2);
00364
00365         L4Re::chkcap(registry->register_irq_obj(&_host_irq),
00366                     "Register irq object");
00367
00368         Features hf(0);
00369         hf.ring_indirect_desc() = true;
00370
00371         _dev_config.host_features(0) = hf.raw;
00372
00373         _dev_config.set_host_feature(L4VIRTIO_FEATURE_VERSION_1);
00374         _dev_config.reset_hdr();
00375
00376         reset();
00377     }
00378
00380     void add_proto(l4_uint32_t id, Proto<Scmi_dev> *proto)
00381     { _protos.insert({id, proto}); }
00382
00383     Proto<Scmi_dev> *proto(l4_uint32_t id) const
00384     {
00385         if (_protos.find(id) != _protos.end())
00386             return _protos.at(id);
00387         return nullptr;
00388     }
00389
00390     void notify_queue(L4virtio::Virtqueue *queue)
00391     {
00392         if (queue->no_notify_guest())
00393             return;
00394
00395         _dev_config.add_irq_status(L4VIRTIO_IRQ_STATUS_VRING);
00396         _kick_guest_irq->trigger();
00397     }
00398
00399 private:
00400     L4::Cap<L4::Irq> device_notify_irq() const override
00401     { return L4::cap_cast<L4::Irq>(_host_irq.obj_cap()); }
00402
00403     void register_single_driver_irq() override
00404     {
00405         _kick_guest_irq = L4Re::Util::Unique_cap<L4::Irq>(
00406             L4Re::chkcap(server_iface()->template rcv_cap<L4::Irq>(0)));
00407
00408         L4Re::chksys(server_iface()->realloc_rcv_cap(0));
00409     }
00410
00411     void kick()
00412     {
00413         if (_request_worker.handle_request() < 0)
00414             device_error();
00415     }
00416
00417     void reset() override
00418     {
00419         for (Virtqueue &q : _q)
00420             q.disable();
00421
00422         for (l4_uint32_t i = 0; i < _dev_config.num_queues(); i++)
00423             reset_queue_config(i, Queue_size);
00424     }
00425
00426     bool check_queues() override
00427     {
00428         return true;
00429     }
00430
00431     int reconfig_queue(unsigned idx) override
00432     {
00433         if (idx >= sizeof(_q) / sizeof(_q[0]))
00434             return -L4_ERANGE;
00435     }

```

```

00436     return setup_queue(_q + idx, idx, Queue_size);
00437 }
00438
00439 void trigger_driver_config_irq() override
00440 {
00441     _dev_config.add_irq_status(L4VIRTIO_IRQ_STATUS_CONFIG);
00442     _kick_guest_irq->trigger();
00443 }
00444
00445 L4virtio::Svr::Dev_config_t<L4virtio::Svr::No_custom_data> _dev_config;
00446 Host_irq _host_irq;
00447 L4Re::Util::Unique_cap<L4::Irq> _kick_guest_irq;
00448 Virtqueue _q[1];
00449 Queue_worker<Scmi_dev> _request_worker;
00450 std::map<L4_uint32_t, Proto<Scmi_dev> *> _protos;
00451 };
00452
00453 class Base_proto : public Proto<Scmi_dev>
00454 {
00455     virtual L4_int32_t fill_attr(Base_attr_t *attr) const = 0;
00456
00457     virtual std::vector<L4_uint32_t> prots() const = 0;
00458
00459     L4_ssize_t handle_request(Scmi_hdr_t &hdr, Data_buffer &buf,
00460                               Queue_worker<Scmi_dev> *qw) override
00461     {
00462         L4_ssize_t total = 0;
00463         L4_ssize_t res = 0;
00464         switch (hdr.message_id())
00465         {
00466             case Protocol_version:
00467             {
00468                 if ((res = qw->write(&buf, &hdr)) < 0)
00469                     return res;
00470                 total += res;
00471
00472                 struct
00473                 {
00474                     L4_int32_t status = Success;
00475                     L4_uint32_t version = Version;
00476                 } version;
00477                 if ((res = qw->write(&buf, &version)) < 0)
00478                     return res;
00479                 total += res;
00480                 break;
00481             }
00482             case Protocol_attributes:
00483             {
00484                 if ((res = qw->write(&buf, &hdr)) < 0)
00485                     return res;
00486                 total += res;
00487
00488                 Base_attr_t ba;
00489                 L4_int32_t status = fill_attr(&ba);
00490                 if ((res = qw->write(&buf, &status)) < 0)
00491                     return res;
00492                 total += res;
00493                 if (status == Success)
00494                 {
00495                     if ((res = qw->write(&buf, &ba)) < 0)
00496                         return res;
00497                     total += res;
00498                 }
00499                 break;
00500             }
00501             case Protocol_message_attributes:
00502             {
00503                 L4_uint32_t msg_id = 0;
00504                 if ((res = qw->read(&buf, &msg_id)) < 0)
00505                     return res;
00506
00507                 if ((res = qw->write(&buf, &hdr)) < 0)
00508                     return res;
00509                 total += res;
00510
00511                 struct
00512                 {
00513                     L4_int32_t status = Not_found;
00514                     L4_uint32_t attr = 0;
00515                 } attr;
00516                 if (msg_id >= Protocol_version &&
00517                     msg_id <= Base_discover_list_protocols)
00518                     attr.status = Success;
00519
00520                 if ((res = qw->write(&buf, &attr)) < 0)
00521                     return res;
00522                 total += res;
00523             }
00524         }
00525     }
00526 }

```

```

00531         break;
00532     }
00533     case Base_discover_vendor:
00534     {
00535         if ((res = qw->write(&buf, &hdr)) < 0)
00536             return res;
00537         total += res;
00538
00539         struct
00540         {
00541             14_int32_t status = Success;
00542             14_uint8_t vendor_identifiier[16] = { "L4Re" };
00543         } vendor;
00544         if ((res = qw->write(&buf, &vendor)) < 0)
00545             return res;
00546         total += res;
00547         break;
00548     }
00549     case Base_discover_sub_vendor:
00550     {
00551         if ((res = qw->write(&buf, &hdr)) < 0)
00552             return res;
00553         total += res;
00554
00555         struct
00556         {
00557             14_int32_t status = Success;
00558             14_uint8_t vendor_identifiier[16] = { "Scmi" };
00559         } vendor;
00560         if ((res = qw->write(&buf, &vendor)) < 0)
00561             return res;
00562         total += res;
00563         break;
00564     }
00565     case Base_discover_implementation_version:
00566     {
00567         if ((res = qw->write(&buf, &hdr)) < 0)
00568             return res;
00569         total += res;
00570
00571         struct
00572         {
00573             14_int32_t status = Success;
00574             14_uint32_t version = 1;
00575         } version;
00576         if ((res = qw->write(&buf, &version)) < 0)
00577             return res;
00578         total += res;
00579         break;
00580     }
00581     case Base_discover_list_protocols:
00582     {
00583         14_uint32_t skip = 0;
00584         if ((res = qw->read(&buf, &skip)) < 0)
00585             return res;
00586
00587         if ((res = qw->write(&buf, &hdr)) < 0)
00588             return res;
00589         total += res;
00590
00591         auto p = prots();
00592         struct
00593         {
00594             14_int32_t status = Success;
00595             14_uint32_t num;
00596         } proto;
00597         proto.num = p.size();
00598         if ((res = qw->write(&buf, &proto)) < 0)
00599             return res;
00600         total += res;
00601
00602         // Array of uint32 where 4 protos are packed into one uint32. So
00603         // round up to 4 bytes and fill the array byte by byte.
00604         14_uint8_t parr[(p.size() + 3) / 4 * 4] = { 0 };
00605         for (14_size_t i = 0; i < p.size(); i++)
00606             parr[i] = p.at(i);
00607
00608         if ((res = qw->write(&buf, parr, sizeof(parr))) < 0)
00609             return res;
00610         total += res;
00611         break;
00612     }
00613     default:
00614     {
00615         if ((res = qw->write(&buf, &hdr)) < 0)
00616             return res;
00617         total += res;

```

```

00618
00619         l4_int32_t status = Not_supported;
00620         if ((res = qw->write(&buf, &status)) < 0)
00621             return res;
00622         total += res;
00623         break;
00624     }
00625 }
00626
00627 return total;
00628 }
00629 };
00630
00631 class Perf_proto : public Proto<Scmi_dev>
00632 {
00633     virtual l4_int32_t fill_attr(Performance_attr_t *attr) const = 0;
00634     virtual l4_int32_t fill_domain_attr(l4_uint32_t domain_id,
00635                                         Performance_domain_attr_t *attr) const = 0;
00636     virtual l4_int32_t fill_describe_levels_n(l4_uint32_t domain_id,
00637                                               l4_uint32_t level_idx,
00638                                               Performance_describe_levels_n_t *attr) const = 0;
00639     virtual l4_int32_t fill_describe_levels(l4_uint32_t domain_id,
00640                                             l4_uint32_t level_idx,
00641                                             l4_uint32_t num,
00642                                             Performance_describe_level_t *attr) const = 0;
00643     virtual l4_int32_t level_set(l4_uint32_t domain_id,
00644                                 l4_uint32_t perf_level) = 0;
00645     virtual l4_int32_t level_get(l4_uint32_t domain_id,
00646                                 l4_uint32_t *perf_level) const = 0;
00647     l4_ssize_t handle_request(Scmi_hdr_t &hdr, Data_buffer &buf,
00648                               Queue_worker<Scmi_dev> *qw) override
00649     {
00650         l4_ssize_t total = 0;
00651         l4_ssize_t res = 0;
00652         switch (hdr.message_id())
00653         {
00654             case Protocol_version:
00655             {
00656                 if ((res = qw->write(&buf, &hdr)) < 0)
00657                     return res;
00658                 total += res;
00659
00660                 struct
00661                 {
00662                     l4_int32_t status = Success;
00663                     l4_uint32_t version = Version;
00664                 } version;
00665                 if ((res = qw->write(&buf, &version)) < 0)
00666                     return res;
00667                 total += res;
00668                 break;
00669             }
00670             case Protocol_attributes:
00671             {
00672                 if ((res = qw->write(&buf, &hdr)) < 0)
00673                     return res;
00674                 total += res;
00675
00676                 Performance_attr_t pa;
00677                 l4_int32_t status = fill_attr(&pa);
00678                 if ((res = qw->write(&buf, &status)) < 0)
00679                     return res;
00680                 total += res;
00681                 if (status == Success)
00682                 {
00683                     if ((res = qw->write(&buf, &pa)) < 0)
00684                         return res;
00685                     total += res;
00686                 }
00687                 break;
00688             }
00689             case Protocol_message_attributes:
00690             {
00691                 l4_uint32_t msg_id = 0;
00692                 if ((res = qw->read(&buf, &msg_id)) < 0)
00693                     return res;
00694
00695                 if ((res = qw->write(&buf, &hdr)) < 0)
00696                     return res;
00697                 total += res;
00698             }
00699         }
00700     }

```

```

00745     struct
00746     {
00747         l4_int32_t status = Not_found;
00748
00749         l4_uint32_t attr_raw = 0;
00750         CXX_BITFIELD_MEMBER(0, 0, fast_channel, attr_raw); // ignored
00751     } attr;
00752     if ((msg_id >= Protocol_version &&
00753         msg_id <= Performance_describe_levels) ||
00754         (msg_id >= Performance_level_set &&
00755         msg_id <= Performance_level_get))
00756         attr.status = Success;
00757
00758     if ((res = qw->write(&buf, &attr)) < 0)
00759         return res;
00760     total += res;
00761     break;
00762 }
00763 case Performance_domain_attributes:
00764 {
00765     l4_uint32_t domain_id = 0;
00766     if ((res = qw->read(&buf, &domain_id)) < 0)
00767         return res;
00768
00769     if ((res = qw->write(&buf, &hdr)) < 0)
00770         return res;
00771     total += res;
00772
00773     Performance_domain_attr_t attr;
00774     l4_int32_t status = fill_domain_attr(domain_id, &attr);
00775     if ((res = qw->write(&buf, &status)) < 0)
00776         return res;
00777     total += res;
00778     if (status == Success)
00779     {
00780         if ((res = qw->write(&buf, &attr)) < 0)
00781             return res;
00782         total += res;
00783     }
00784     break;
00785 }
00786 case Performance_describe_levels:
00787 {
00788     struct
00789     {
00790         l4_uint32_t domain_id = 0;
00791         l4_uint32_t level_idx = 0;
00792     } param;
00793     if ((res = qw->read(&buf, &param)) < 0)
00794         return res;
00795
00796     if ((res = qw->write(&buf, &hdr)) < 0)
00797         return res;
00798     total += res;
00799
00800     // First figure out how many levels we support
00801     Performance_describe_levels_n_t attr;
00802     l4_int32_t status = fill_describe_levels_n(param.domain_id, param.level_idx,
00803                                             &attr);
00804     if (status != Success)
00805     {
00806         // On error bail out early
00807         if ((res = qw->write(&buf, &status)) < 0)
00808             return res;
00809         total += res;
00810         break;
00811     }
00812
00813     // Now fetch the actual levels
00814     Performance_describe_level_t attr1[attr.nperf_levels().get()];
00815     status = fill_describe_levels(param.domain_id, param.level_idx,
00816                                 attr.nperf_levels(), attr1);
00817     if ((res = qw->write(&buf, &status)) < 0)
00818         return res;
00819     total += res;
00820     if (status == Success)
00821     {
00822         // Write both answers to the client
00823         if ((res = qw->write(&buf, &attr)) < 0)
00824             return res;
00825         total += res;
00826         if ((res = qw->write(&buf, attr1, sizeof(attr1))) < 0)
00827             return res;
00828         total += res;
00829     }
00830     break;
00831 }

```

```

00832     case Performance_level_set:
00833     {
00834         struct
00835         {
00836             l4_uint32_t domain_id;
00837             l4_uint32_t perf_level;
00838         } param;
00839         if ((res = qw->read(&buf, &param)) < 0)
00840             return res;
00841
00842         if ((res = qw->write(&buf, &hdr)) < 0)
00843             return res;
00844         total += res;
00845
00846         l4_int32_t status = level_set(param.domain_id, param.perf_level);
00847         if ((res = qw->write(&buf, &status)) < 0)
00848             return res;
00849         total += res;
00850         break;
00851     }
00852     case Performance_level_get:
00853     {
00854         l4_uint32_t domain_id = 0;
00855         if ((res = qw->read(&buf, &domain_id)) < 0)
00856             return res;
00857
00858         if ((res = qw->write(&buf, &hdr)) < 0)
00859             return res;
00860         total += res;
00861
00862         l4_uint32_t perf_level;
00863         l4_int32_t status = level_get(domain_id, &perf_level);
00864         if ((res = qw->write(&buf, &status)) < 0)
00865             return res;
00866         total += res;
00867         if (status == Success)
00868         {
00869             if ((res = qw->write(&buf, &perf_level)) < 0)
00870                 return res;
00871             total += res;
00872         }
00873         break;
00874     }
00875     default:
00876     {
00877         if ((res = qw->write(&buf, &hdr)) < 0)
00878             return res;
00879         total += res;
00880
00881         l4_int32_t status = Not_supported;
00882         if ((res = qw->write(&buf, &status)) < 0)
00883             return res;
00884         total += res;
00885         break;
00886     }
00887 }
00888 return total;
00889 }
00890 };
00891
00892 } /* Scmi */ } /* Svr */ } /* L4virtio */

```

## 16.269 virtio-spi-device

```

00001 // vi:set ft=c++: -- Mode: C++ --
00002 /*
00003  * Copyright (C) 2025 Kernkonzept GmbH.
00004  * Author(s): Martin Kuettler <martin.kuettler@kernkonzept.com>
00005  *           Jakub Jermar <jakub.jermar@kernkonzept.com>
00006  *
00007  * License: see LICENSE.spdx (in this directory or the directories above)
00008  */
00009
00010 #pragma once
00011
00012 #include <l4/re/error_helper>
00013 #include <l4/sys/cxx/ipc_epiface>
00014
00015 #include <l4/l4virtio/server/virtio>
00016 #include <l4/l4virtio/server/l4virtio>
00017 #include <l4/l4virtio/l4virtio>
00018
00019 #include <l4/re/error_helper>

```



```

00020 #include <l4/re/util/object_registry>
00021 #include <l4/re/util/br_manager>
00022 #include <l4/sys/cxx/ipc_epiface>
00023
00024 #include <vector>
00025 #include <l4/cxx/pair>
00026
00027 namespace L4virtio {
00028 namespace Svr {
00029
00030 struct Spi_config
00031 {
00032     l4_uint8_t cs_max_number;
00033     l4_uint8_t cs_change_supported;
00034     l4_uint8_t tx_nbits_supported;
00035     l4_uint8_t rx_nbits_supported;
00036     l4_uint32_t bits_per_word_mask;
00037     l4_uint32_t mode_func_supported;
00038     l4_uint32_t max_freq_hz;
00039     l4_uint32_t max_word_delay_ns;
00040     l4_uint32_t max_cs_setup_ns;
00041     l4_uint32_t max_cs_hold_ns;
00042     l4_uint32_t max_cs_inactive_ns;
00043 };
00044
00045 enum Spi_transfer_result: l4_uint8_t
00046 {
00047     Spi_trans_ok = 0,
00048     Spi_param_err = 1,
00049     Spi_trans_err = 2,
00050 };
00051
00052 struct Spi_transfer_head
00053 {
00054     l4_uint8_t chip_select_id;
00055     l4_uint8_t bits_per_word;
00056     l4_uint8_t cs_change;
00057     l4_uint8_t tx_nbits;
00058     l4_uint8_t rx_nbits;
00059     l4_uint8_t last_request; // XXX non-standard! aka reserved[0]
00060     l4_uint8_t reserved[2];
00061     l4_uint32_t mode;
00062     l4_uint32_t freq;
00063     l4_uint32_t word_delay_ns;
00064     l4_uint32_t cs_setup_ns;
00065     l4_uint32_t cs_delay_hold_ns;
00066     l4_uint32_t cs_change_delay_inactive_ns;
00067 };
00068 static_assert(sizeof(Spi_transfer_head) == 32,
00069               "Spi_transfer_head contains padding bytes.");
00070
00071 struct Spi_transfer_req
00072 {
00073     struct Spi_transfer_head head;
00074     l4_uint8_t *tx_buf = nullptr;
00075     l4_uint8_t *rx_buf = nullptr;
00076     Spi_transfer_result *result = nullptr;
00077
00078     unsigned tx_size = 0;
00079     unsigned rx_size = 0;
00080
00081     void set_result(Spi_transfer_result res)
00082     {
00083         *result = res;
00084     }
00085 };
00086
00100 template <typename Spi_request_handler, typename Epiface = L4virtio::Device>
00101 class Virtio_spi
00102 : public L4virtio::Svr::Device,
00103   public L4::Epiface_t<Virtio_spi<Spi_request_handler, Epiface>, Epiface>
00104 {
00105 private:
00106     enum
00107     {
00108         Num_request_queues = 1,
00109         Queue_size = 128,
00110     };
00111
00112 public:
00118     class Host_irq : public L4::Irqep_t<Host_irq>
00119     {
00120     public:
00121         explicit Host_irq(Virtio_spi *spi) : L4::Irqep_t<Host_irq>(), _spi(spi) {}
00122
00123         void handle_irq()
00124         {

```

```

00125     _spi->handle_queue();
00126 }
00127
00128 private:
00129     Virtio_spi *_spi;
00130 };
00131
00132 class Request_processor : public L4virtio::Svr::Request_processor
00133 {
00134 public:
00135     struct Data_buffer : public L4virtio::Svr::Data_buffer
00136     {
00137         Data_buffer()
00138         {
00139             pos = nullptr;
00140             left = 0;
00141         }
00142         // This constructor is called from within the base start(), so make it
00143         // available.
00144         Data_buffer(L4virtio::Svr::Driver_mem_region const *r,
00145                     L4virtio::Svr::Virtqueue::Desc const &d,
00146                     L4virtio::Svr::Request_processor const *)
00147         {
00148             pos = static_cast<char *>(r->local(d.addr));
00149             left = d.len;
00150         }
00151     };
00152
00153     Request_processor(L4virtio::Svr::Virtqueue *q, Spi_request_handler *hndlr,
00154                      Virtio_spi *spi)
00155     : _q(q), _req_handler(hndlr), _spi(spi), _head(), _req()
00156     {}
00157
00158     bool init_queue()
00159     {
00160         auto r = _q->next_avail();
00161
00162         if (L4_UNLIKELY(!r))
00163             return false;
00164
00165         _head = start(_spi->mem_info(), r, &_req);
00166
00167         return true;
00168     }
00169
00170     Spi_transfer_req get_request()
00171     {
00172         Spi_transfer_req request;
00173         memcpy(&request.head, _req.pos, sizeof(Spi_transfer_head));
00174
00175         // Check for a TX and/or RX buffer
00176         if (!next(_spi->mem_info(), &_req))
00177         {
00178             L4Re::throw_error(-L4_EIO, "Virtio SPI request too short");
00179         }
00180
00181         if (current_flags().write())
00182         {
00183             // device-writable buffer
00184             request.rx_buf = reinterpret_cast<l4_uint8_t *>(_req.pos);
00185             request.rx_size = _req.left;
00186         }
00187         else
00188         {
00189             request.tx_buf = reinterpret_cast<l4_uint8_t *>(_req.pos);
00190             request.tx_size = _req.left;
00191         }
00192
00193         // Check for an RX buffer or request result buffer
00194         if (!next(_spi->mem_info(), &_req))
00195         {
00196             L4Re::throw_error(-L4_EIO, "Virtio SPI request too short");
00197         }
00198
00199         if (has_more())
00200         {
00201             // This must be the RX buffer
00202             if (request.rx_buf || !current_flags().write())
00203             {
00204                 L4Re::throw_error(-L4_EIO, "Bad Virtio SPI request");
00205             }
00206
00207             request.rx_buf = reinterpret_cast<l4_uint8_t *>(_req.pos);
00208             request.rx_size = _req.left;
00209             next(_spi->mem_info(), &_req);
00210         }
00211     }

```

```

00225     }
00226
00227     request.result = reinterpret_cast<Spi_transfer_result *>(_req.pos);
00228
00229     return request;
00230 }
00231
00232 void handle_request()
00233 {
00234     if (!_head)
00235         if (!init_queue())
00236             return;
00237
00238     using Consumed_entry =
00239         cxx::Pair<L4virtio::Svr::Virtqueue::Head_desc, l4_uint32_t>;
00240     std::vector<Consumed_entry> consumed;
00241
00242     for (;;)
00243     {
00244         auto r = get_request();
00245         Spi_transfer_result res;
00246         if (r.tx_buf && r.rx_buf && (r.tx_size != r.rx_size))
00247             res = Spi_param_err;
00248         else
00249             res =
00250                 _req_handler->handle_transfer(r.head, r.tx_buf, r.rx_buf,
00251                     r.tx_size ? r.tx_size : r.rx_size);
00252         r.set_result(res);
00253
00254         l4_uint32_t written = sizeof(Spi_transfer_result);
00255         if (res == Spi_trans_ok)
00256             written += r.rx_size;
00257
00258         consumed.emplace_back(_head, written);
00259         if (!init_queue())
00260             break;
00261     }
00262
00263     _q->finish(consumed.begin(), consumed.end(), _spi);
00264
00265     _head = Virtqueue::Head_desc();
00266 }
00267
00268 private:
00269     L4virtio::Svr::Virtqueue *_q;
00270     Spi_request_handler *_req_handler;
00271     Virtio_spi *_spi;
00272     L4virtio::Svr::Virtqueue::Head_desc _head;
00273     Data_buffer _req;
00274 };
00275
00276 Virtio_spi(Spi_request_handler *hndlr, L4Re::Util::Object_registry *registry)
00277 : L4virtio::Svr::Device(&_dev_config),
00278   _dev_config(L4VIRTIO_VENDOR_KK, L4VIRTIO_ID_SPI, Num_request_queues),
00279   _req_handler(hndlr),
00280   _host_irq(this),
00281   _request_processor(&_q, hndlr, this)
00282 {
00283     init_mem_info(2);
00284     reset_queue_config(0, Queue_size);
00285     setup_queue(&_q, 0, Queue_size);
00286     registry->register_irq_obj(&_host_irq);
00287
00288     Spi_config volatile *pc = _dev_config.priv_config();
00289
00290     pc->cs_max_number = hndlr->cs_max_number();
00291     pc->cs_change_supported = 0;
00292     pc->tx_nbits_supported = 0;
00293     pc->rx_nbits_supported = 0;
00294     pc->bits_per_word_mask = 0x80;
00295     pc->mode_func_supported = hndlr->mode_func_supported();
00296     pc->max_freq_hz = 0; // XXX: restrict wrt. controller
00297     pc->max_word_delay_ns = 0;
00298     pc->max_cs_setup_ns = 0;
00299     pc->max_cs_hold_ns = 0;
00300     pc->max_cs_inactive_ns = 0;
00301
00302     L4virtio::Svr::Dev_config::Features hf(0);
00303     _dev_config.host_features(0) = hf.raw;
00304     _dev_config.set_host_feature(L4VIRTIO_FEATURE_VERSION_1);
00305     _dev_config.reset_hdr();
00306 }
00307
00308 void notify_queue(L4virtio::Svr::Virtqueue *)
00309 {
00310     if (_q.no_notify_guest())
00311         return;

```

```

00312
00313     _dev_config.add_irq_status(L4VIRTIO_IRQ_STATUS_VRING);
00314     L4Re::chkipc(_notify_guest_irq->trigger(), "trigger guest irq");
00315 }
00316
00317 void handle_queue()
00318 {
00319     _request_processor.handle_request();
00320 }
00321
00322 void reset() override
00323 {
00324 }
00325
00326 bool check_queues() override
00327 {
00328     return true;
00329 }
00330
00331 int reconfig_queue(unsigned idx) override
00332 {
00333     if (idx != 0)
00334         return -L4_ERANGE;
00335
00336     setup_queue(&_q, 0, Queue_size);
00337
00338     return L4_EOK;
00339 }
00340
00341 void trigger_driver_config_irq() override
00342 {
00343     _dev_config.add_irq_status(L4VIRTIO_IRQ_STATUS_CONFIG);
00344     _notify_guest_irq->trigger();
00345 }
00346
00347 L4::Ipc_svr::Server_iface *server_iface() const override
00348 {
00349     return L4::Epiface::server_iface();
00350 }
00351
00352 long op_set_status(L4virtio::Device::Rights r, unsigned status)
00353 {
00354     return L4virtio::Svr::Device::op_set_status(r, status);
00355 }
00356
00357 long op_config_queue(L4virtio::Device::Rights r, unsigned queue)
00358 {
00359     return L4virtio::Svr::Device::op_config_queue(r, queue);
00360 }
00361
00362 long op_device_config(L4virtio::Device::Rights r,
00363                      L4::Ipc::Cap<L4Re::Dataspace> &config_ds,
00364                      l4_addr_t &ds_offset)
00365 {
00366     return L4virtio::Svr::Device::op_device_config(r, config_ds, ds_offset);
00367 }
00368
00369 L4::Cap<L4::Irq> device_notify_irq() const override
00370 {
00371     return L4::cap_cast<L4::Irq>(_host_irq.obj_cap());
00372 }
00373
00374 void register_single_driver_irq() override
00375 {
00376     _notify_guest_irq =
00377         L4Re::chkcap(server_iface()->template_rcv_cap<L4::Irq>(0));
00378
00379     L4Re::chksys(server_iface()->realloc_rcv_cap(0));
00380 }
00381
00382
00383 private:
00384     L4virtio::Svr::Dev_config_t<Spi_config> _dev_config;
00385     Spi_request_handler *_req_handler;
00386     L4virtio::Svr::Virtqueue _q;
00387     Host_irq _host_irq;
00388     L4::Cap<L4::Irq> _notify_guest_irq;
00389     Request_processor _request_processor;
00390 };
00391
00392 } // namespace Svr
00393 } // namespace L4virtio

```

## 16.270 virtio.h

```

00001 /* SPDX-License-Identifier: MIT */
00002 /*
00003  * Copyright (C) 2013-2022, 2024-2025 Kernkonzept GmbH.
00004  * Author(s): Alexander Warg <alexander.warg@kernkonzept.com>
00005  *           Matthias Lange <matthias.lange@kernkonzept.com>
00006  *
00007  */
00008 #pragma once
00009
00013
00027
00028 #include <14/sys/compiler.h>
00029 #include <14/sys/utcb.h>
00030 #include <14/sys/ipc.h>
00031 #include <14/sys/types.h>
00032
00034 enum L4_virtio_protocol
00035 {
00036     L4VIRTIO_PROTOCOL = 0,
00037 };
00038
00039 enum L4virtio_magic
00040 {
00041     L4VIRTIO_MAGIC = 0x74726976
00042 };
00043
00044 enum L4virtio_vendor
00045 {
00046     L4VIRTIO_VENDOR_KK = 0x44
00047 };
00048
00052 enum L4_virtio_opcodes
00053 {
00054     L4VIRTIO_OP_SET_STATUS      = 0,
00055     L4VIRTIO_OP_CONFIG_QUEUE    = 1,
00056     L4VIRTIO_OP_REGISTER_DS     = 3,
00057     L4VIRTIO_OP_DEVICE_CONFIG   = 4,
00058     L4VIRTIO_OP_GET_DEVICE_IRQ  = 5,
00059 };
00060
00062 enum L4virtio_device_ids
00063 {
00064     L4VIRTIO_ID_NET              = 1,
00065     L4VIRTIO_ID_BLOCK            = 2,
00066     L4VIRTIO_ID_CONSOLE         = 3,
00067     L4VIRTIO_ID_RNG             = 4,
00068     L4VIRTIO_ID_BALLOON         = 5,
00069     L4VIRTIO_ID_RPMMSG          = 7,
00070     L4VIRTIO_ID_SCSI            = 8,
00071     L4VIRTIO_ID_9P              = 9,
00072     L4VIRTIO_ID_RPROC_SERIAL    = 11,
00073     L4VIRTIO_ID_CAIF            = 12,
00074     L4VIRTIO_ID_GPU             = 16,
00075     L4VIRTIO_ID_INPUT           = 18,
00076     L4VIRTIO_ID_VSOCK           = 19,
00077     L4VIRTIO_ID_CRYPT           = 20,
00078     L4VIRTIO_ID_FS              = 26,
00079     L4VIRTIO_ID_SCSI            = 32,
00080     L4VIRTIO_ID_I2C             = 34,
00081     L4VIRTIO_ID_WATCHDOG        = 35,
00082     L4VIRTIO_ID_CAN             = 36,
00083     L4VIRTIO_ID_GPIO            = 41,
00084     L4VIRTIO_ID_SPI             = 45,
00085
00086     L4VIRTIO_ID_SOCKET          = 0x9999,
00087 };
00088
00090 enum L4virtio_device_status
00091 {
00092     L4VIRTIO_STATUS_ACKNOWLEDGE = 1,
00093     L4VIRTIO_STATUS_DRIVER      = 2,
00094     L4VIRTIO_STATUS_DRIVER_OK   = 4,
00095     L4VIRTIO_STATUS_FEATURES_OK = 8,
00096     L4VIRTIO_STATUS_DEVICE_NEEDS_RESET = 0x40,
00097     L4VIRTIO_STATUS_FAILED      = 0x80
00098 };
00099
00101 enum L4virtio_feature_bits
00102 {
00104     L4VIRTIO_FEATURE_VERSION_1 = 32,
00106     L4VIRTIO_FEATURE_CMD_CONFIG = 160
00107 };
00108
00113 enum L4_virtio_irq_status

```

```

00114 {
00115     L4VIRTIO_IRQ_STATUS_VRING = 1,
00116     L4VIRTIO_IRQ_STATUS_CONFIG = 2,
00117 };
00118
00122 enum L4_virtio_cmd
00123 {
00124     L4VIRTIO_CMD_NONE = 0x00000000,
00125     L4VIRTIO_CMD_SET_STATUS = 0x01000000,
00126     L4VIRTIO_CMD_CFG_QUEUE = 0x02000000,
00127     L4VIRTIO_CMD_CFG_CHANGED = 0x04000000,
00128     L4VIRTIO_CMD_NOTIFY_QUEUE = 0x08000000,
00129     L4VIRTIO_CMD_MASK = 0xff000000,
00130 };
00131
00135 typedef struct l4virtio_config_hdr_t
00136 {
00137     /* Virtio(0x00): device config */
00138     l4_uint32_t magic;
00139     l4_uint32_t version;
00140     l4_uint32_t device;
00141     l4_uint32_t vendor;
00142
00143     /* Virtio(0x10): device features */
00144     l4_uint32_t dev_features;
00145     l4_uint32_t dev_features_sel;
00146     l4_uint32_t _res1[2];
00147
00148     /* Virtio(0x20): driver features */
00149     l4_uint32_t driver_features;
00150     l4_uint32_t driver_features_sel;
00151
00152     /* L4Virtio(0x28): L4 queue */
00153     l4_uint32_t num_queues;
00154     l4_uint32_t queues_offset;
00155
00156     /* Virtio(0x30): queue status */
00157     l4_uint32_t queue_sel;
00158     l4_uint32_t queue_num_max;
00159     l4_uint32_t queue_num;
00160     l4_uint32_t _res3[2];
00161     l4_uint32_t queue_ready;
00162     l4_uint32_t _res4[2];
00163
00164     /* Virtio(0x50): queue notify */
00165     l4_uint32_t queue_notify;
00166     l4_uint32_t _res5[3];
00167
00168     /* Virtio(0x60): interrupt handling */
00169     l4_uint32_t irq_status;
00170     l4_uint32_t irq_ack;
00171     l4_uint32_t _res6[2];
00172
00173     /* Virtio(0x70): Device status register (read-only). The register must be
00174      * written using l4virtio_set_status(). */
00175     l4_uint32_t status;
00176
00177     /* L4Virtio(0x74): W: Event index to be used for config notifications (device to driver) */
00178     l4_uint32_t cfg_driver_notify_index;
00179     /* L4Virtio(0x78): R: Event index to be used for config notifications (driver to device) */
00180     l4_uint32_t cfg_device_notify_index;
00181
00182     /* L4Virtio(0x7c): L4 specific command register polled by the driver iff supported */
00183     l4_uint32_t cmd;
00184
00185     /* Virtio(0x80): queue descriptors */
00186     l4_uint64_t queue_desc;
00187     l4_uint32_t _res8[2];
00188     l4_uint64_t queue_avail;
00189     l4_uint32_t _res9[2];
00190     l4_uint64_t queue_used;
00191
00192     l4_uint32_t _res10[1];
00193
00194     /* Virtio(0xac): shared memory region */
00195     l4_uint32_t shm_sel;
00196     l4_uint64_t shm_len;
00197     l4_uint64_t shm_base;
00198
00199     /* L4Virtio(0xc0): use the unused space here for device and driver feature bitmaps */
00200     l4_uint32_t dev_features_map[6];
00201     l4_uint32_t _res11[2];
00202     l4_uint32_t driver_features_map[6];
00203     l4_uint32_t _res12[1];
00204
00205     /* Virtio(0xfc): config generation */
00206     l4_uint32_t generation;

```

```

00207 } l4virtio_config_hdr_t;
00208
00226 typedef struct l4virtio_config_queue_t
00227 {
00229     l4_uint16_t num_max;
00231     l4_uint16_t num;
00232
00234     l4_uint16_t ready;
00235
00237     l4_uint16_t driver_notify_index;
00238
00239     l4_uint64_t desc_addr;
00240     l4_uint64_t avail_addr;
00241     l4_uint64_t used_addr;
00242
00244     l4_uint16_t device_notify_index;
00245 } l4virtio_config_queue_t;
00246
00247 L4_BEGIN_DECLS
00248
00254 L4_INLINE l4virtio_config_queue_t *
00255 l4virtio_config_queues(l4virtio_config_hdr_t const *cfg)
00256 {
00257     return (l4virtio_config_queue_t *)(((l4_addr_t)cfg) + cfg->queues_offset);
00258 }
00259
00265 L4_INLINE void *
00266 l4virtio_device_config(l4virtio_config_hdr_t const *cfg)
00267 {
00268     return (void *)(((l4_addr_t)cfg) + 0x100);
00269 }
00270
00274 L4_INLINE void
00275 l4virtio_set_feature(l4_uint32_t *feature_map, unsigned feat)
00276 {
00277     unsigned idx = feat / 32;
00278
00279     if (idx < 8)
00280         feature_map[idx] |= 1UL << (feat % 32);
00281 }
00282
00286 L4_INLINE void
00287 l4virtio_clear_feature(l4_uint32_t *feature_map, unsigned feat)
00288 {
00289     unsigned idx = feat / 32;
00290
00291     if (idx < 8)
00292         feature_map[idx] &= ~(1UL << (feat % 32));
00293 }
00294
00298 L4_INLINE unsigned
00299 l4virtio_get_feature(l4_uint32_t *feature_map, unsigned feat)
00300 {
00301     unsigned idx = feat / 32;
00302
00303     if (idx >= 8)
00304         return 0;
00305
00306     return feature_map[idx] & (1UL << (feat % 32));
00307 }
00308
00314 L4_CV int
00315 l4virtio_set_status(l4_cap_idx_t cap, unsigned status) L4_NOTHROW;
00316
00322 L4_CV int
00323 l4virtio_config_queue(l4_cap_idx_t cap, unsigned queue) L4_NOTHROW;
00324
00330 L4_CV int
00331 l4virtio_register_ds(l4_cap_idx_t cap, l4_cap_idx_t ds_cap,
00332                     l4_uint64_t base, l4_umword_t offset,
00333                     l4_umword_t size) L4_NOTHROW;
00334
00340 L4_CV int
00341 l4virtio_device_config_ds(l4_cap_idx_t cap, l4_cap_idx_t config_ds,
00342                           l4_addr_t *ds_offset) L4_NOTHROW;
00343
00349 L4_CV int
00350 l4virtio_device_notification_irq(l4_cap_idx_t cap, unsigned index,
00351                                  l4_cap_idx_t irq) L4_NOTHROW;
00352
00353 L4_END_DECLS
00354

```

## 16.271 virtio\_block.h

```

00001  /* SPDX-License-Identifier: MIT */
00002  /*
00003   * (c) 2014 Sarah Hoffmann <sarah.hoffmann@kernkonzept.com>
00004   */
00005
00006  #pragma once
00007
00013
00014  #include <linux/types.h>
00015
00019  enum L4virtio_block_operations
00020  {
00021      L4VIRTIO_BLOCK_T_IN      = 0,
00022      L4VIRTIO_BLOCK_T_OUT     = 1,
00023      L4VIRTIO_BLOCK_T_FLUSH   = 4,
00024      L4VIRTIO_BLOCK_T_GET_ID  = 8,
00025      L4VIRTIO_BLOCK_T_DISCARD = 11,
00026      L4VIRTIO_BLOCK_T_WRITE_ZEROES = 13,
00027  };
00028
00032  enum L4virtio_block_status
00033  {
00034      L4VIRTIO_BLOCK_S_OK      = 0,
00035      L4VIRTIO_BLOCK_S_IOERR   = 1,
00036      L4VIRTIO_BLOCK_S_UNSUPP  = 2
00037  };
00038
00042  typedef struct l4virtio_block_header_t
00043  {
00044      l4_uint32_t type;
00045      l4_uint32_t ioprio;
00046      l4_uint64_t sector;
00047  } l4virtio_block_header_t;
00048
00049  enum L4virtio_block_discard_flags_t
00050  {
00051      L4VIRTIO_BLOCK_DISCARD_F_UNMAP = 0x00000001UL,
00052      L4VIRTIO_BLOCK_DISCARD_F_RESERVED = 0xFFFFFFF0UL,
00053  };
00054
00058  typedef struct l4virtio_block_discard_t
00059  {
00060      l4_uint64_t sector;
00061      l4_uint32_t num_sectors;
00062      l4_uint32_t flags;
00063  } l4virtio_block_discard_t;
00064
00068  typedef struct l4virtio_block_config_t
00069  {
00070      l4_uint64_t capacity;
00071      l4_uint32_t size_max;
00072      l4_uint32_t seg_max;
00073      struct l4virtio_block_config_geometry_t
00074      {
00075          l4_uint16_t cylinders;
00076          l4_uint8_t heads;
00077          l4_uint8_t sectors;
00078      } geometry;
00079      l4_uint32_t blk_size;
00080      struct l4virtio_block_config_topology_t
00081      {
00083          l4_uint8_t physical_block_exp;
00085          l4_uint8_t alignment_offset;
00087          l4_uint16_t min_io_size;
00089          l4_uint32_t opt_io_size;
00090      } topology;
00091      l4_uint8_t writeback;
00092      l4_uint8_t unused0[1];
00093      l4_uint16_t num_queues;
00094      l4_uint32_t max_discard_sectors;
00095      l4_uint32_t max_discard_seg;
00096      l4_uint32_t discard_sector_alignment;
00097      l4_uint32_t max_write_zeroes_sectors;
00098      l4_uint32_t max_write_zeroes_seg;
00099      l4_uint8_t write_zeroes_may_unmap;
00100      l4_uint8_t unused1[3];
00101  } l4virtio_block_config_t;
00102
00104  enum L4virtio_block_feature_bits
00105  {
00106      L4VIRTIO_BLOCK_F_SIZE_MAX = 1,
00107      L4VIRTIO_BLOCK_F_SEG_MAX = 2,
00108      L4VIRTIO_BLOCK_F_GEOMETRY = 4,
00109      L4VIRTIO_BLOCK_F_RO = 5,

```



```

00110     L4VIRTIO_BLOCK_F_BLK_SIZE = 6,
00111     L4VIRTIO_BLOCK_F_FLUSH = 9,
00112     L4VIRTIO_BLOCK_F_TOPOLOGY = 10,
00113     L4VIRTIO_BLOCK_F_CONFIG_WCE = 11,
00114     L4VIRTIO_BLOCK_F_DISCARD = 13,
00115     L4VIRTIO_BLOCK_F_WRITE_ZEROES = 14,
00116 };
00117

```

## 16.272 virtio\_input.h

```

00001 /* SPDX-License-Identifier: MIT */
00002 /*
00003  * Copyright (C) 2019, 2022, 2024 Kernkonzept GmbH.
00004  * Author(s): Sarah Hoffmann <sarah.hoffmann@kernkonzept.com>
00005  */
00006 #pragma once
00007
00013
00014 #include <l4/sys/types.h>
00015
00019 enum l4virtio_input_config_select
00020 {
00021     L4VIRTIO_INPUT_CFG_UNSET = 0,
00022     L4VIRTIO_INPUT_CFG_ID_NAME = 1,
00023     L4VIRTIO_INPUT_CFG_ID_SERIAL = 2,
00024     L4VIRTIO_INPUT_CFG_ID_DEVIDS = 3,
00025     L4VIRTIO_INPUT_CFG_PROP_BITS = 0x10,
00026     L4VIRTIO_INPUT_CFG_EV_BITS = 0x11,
00027     L4VIRTIO_INPUT_CFG_ABS_INFO = 0x12
00028 };
00029
00033 typedef struct l4virtio_input_absinfo_t
00034 {
00035     l4_uint32_t min;
00036     l4_uint32_t max;
00037     l4_uint32_t fuzz;
00038     l4_uint32_t flat;
00039     l4_uint32_t res;
00040 } l4virtio_absinfo_t;
00041
00045 typedef struct l4virtio_input_devids_t
00046 {
00047     l4_uint16_t bustype;
00048     l4_uint16_t vendor;
00049     l4_uint16_t product;
00050     l4_uint16_t version;
00051 } l4virtio_input_devids_t;
00052
00056 typedef struct l4virtio_input_config_t
00057 {
00058     l4_uint8_t     select;
00059     l4_uint8_t     subssel;
00060     l4_uint8_t     size;
00061     l4_uint8_t     reserved[5];
00062     union
00063     {
00064         char string[128];
00065         l4_uint8_t bitmap[128];
00066         struct l4virtio_input_absinfo_t abs;
00067         struct l4virtio_input_devids_t ids;
00068     } u;
00069 } l4virtio_input_config_t;
00070
00074 typedef struct l4virtio_input_event_t
00075 {
00076     l4_uint16_t type;
00077     l4_uint16_t code;
00078     l4_uint32_t value;
00079 } l4virtio_input_event_t;
00080

```

## 16.273 virtqueue

```

00001 // vi:set ft=c++: -*- Mode: C++ -*-
00002 /* SPDX-License-Identifier: MIT */
00003 /*
00004  * (c) 2014 Alexander Warg <warg@os.inf.tu-dresden.de>

```

```

00005  */
00006
00007 #include <l4/re/util/debug>
00008 #include <l4/sys/types.h>
00009 #include <l4/sys/err.h>
00010 #include <l4/cxx/bitfield>
00011 #include <l4/cxx/exceptions>
00012 #include <cstdint>
00013
00014 #pragma once
00015
00016 namespace L4virtio {
00017
00018 #if defined(__ARM_ARCH) && __ARM_ARCH == 7
00019 static inline void wmb() { asm volatile ("dmb ishst" : : : "memory"); }
00020 static inline void rmb() { asm volatile ("dmb ish" : : : "memory"); }
00021 #elif defined(__ARM_ARCH) && __ARM_ARCH >= 8
00022 static inline void wmb() { asm volatile ("dmb ishst" : : : "memory"); }
00023 static inline void rmb() { asm volatile ("dmb ishld" : : : "memory"); }
00024 #elif defined(__mips__)
00025 static inline void wmb() { asm volatile ("sync" : : : "memory"); }
00026 static inline void rmb() { asm volatile ("sync" : : : "memory"); }
00027 #elif defined(__amd64__) || defined(__i386__) || defined(__i686__)
00028 static inline void wmb() { asm volatile ("sfence" : : : "memory"); }
00029 static inline void rmb() { asm volatile ("lfence" : : : "memory"); }
00030 #elif defined(__riscv)
00031 static inline void wmb() { asm volatile ("fence ow, ow" : : : "memory"); }
00032 static inline void rmb() { asm volatile ("fence ir, ir" : : : "memory"); }
00033 #else
00034 #warning Missing proper memory write barrier
00035 static inline void wmb() { asm volatile ("": : : "memory"); }
00036 static inline void rmb() { asm volatile ("": : : "memory"); }
00037 #endif
00038
00039
00046 template< typename T >
00047 class Ptr
00048 {
00049 public:
00051 enum Invalid_type { Invalid };
00052
00053 Ptr() = default;
00054
00056 Ptr(Invalid_type) : _p(~0ULL) {}
00057
00059 explicit Ptr(l4_uint64_t vm_addr) : _p(vm_addr) {}
00060
00062 l4_uint64_t get() const { return _p; }
00063
00065 bool is_valid() const { return _p != ~0ULL; }
00066
00067 private:
00068 l4_uint64_t _p;
00069 };
00070
00071
00080 class Virtqueue
00081 {
00082 public:
00086 class Desc
00087 {
00088 public:
00092 struct Flags
00093 {
00094 l4_uint16_t raw;
00095 Flags() = default;
00096
00098 explicit Flags(l4_uint16_t v) : raw(v) {}
00099
00101 CXX_BITFIELD_MEMBER( 0, 0, next, raw);
00103 CXX_BITFIELD_MEMBER( 1, 1, write, raw);
00105 CXX_BITFIELD_MEMBER( 2, 2, indirect, raw);
00106 };
00107
00108 Ptr<void> addr;
00109 l4_uint32_t len;
00110 Flags flags;
00111 l4_uint16_t next;
00112
00116 void dump(unsigned idx) const
00117 {
00118 L4Re::Util::Dbg().printf("D[%04x]: %08llx (%x) f=%04x n=%04x\n",
00119 idx, addr.get(),
00120 len, static_cast<unsigned>(flags.raw),
00121 static_cast<unsigned>(next));
00122 }
00123 };

```

```

00124
00128 class Avail
00129 {
00130 public:
00134     struct Flags
00135     {
00136         l4_uint16_t raw;
00137         Flags() = default;
00138
00140         explicit Flags(l4_uint16_t v) : raw(v) {}
00141
00143         CXX_BITFIELD_MEMBER( 0, 0, no_irq, raw);
00144     };
00145
00146     Flags flags;
00147     l4_uint16_t idx;
00148     l4_uint16_t ring[];
00149 };
00150
00154 struct Used_elem
00155 {
00156     Used_elem() = default;
00157
00165     Used_elem(l4_uint16_t id, l4_uint32_t len) : id(id), len(len) {}
00166     l4_uint32_t id;
00167     l4_uint32_t len;
00168 };
00169
00173 class Used
00174 {
00175 public:
00179     struct Flags
00180     {
00181         l4_uint16_t raw;
00182         Flags() = default;
00183
00185         explicit Flags(l4_uint16_t v) : raw(v) {}
00186
00188         CXX_BITFIELD_MEMBER( 0, 0, no_notify, raw);
00189     };
00190
00191     Flags flags;
00192     l4_uint16_t idx;
00193     Used_elem ring[];
00194 };
00195
00196 protected:
00197     Desc *_desc = nullptr;
00198     Avail *_avail = nullptr;
00199     Used *_used = nullptr;
00200
00202     l4_uint16_t _current_avail = 0;
00203
00208     l4_uint16_t _idx_mask = 0;
00209
00213     Virtqueue() = default;
00214
00215     Virtqueue(Virtqueue const &) = delete;
00216     ~Virtqueue() = default;
00217
00218 public:
00224     void disable()
00225     { _desc = 0; }
00226
00230     enum
00231     {
00232         Desc_align = 4, ///< Alignment of the descriptor table.
00233         Avail_align = 1, ///< Alignment of the available ring.
00234         Used_align = 2,  ///< Alignment of the used ring.
00235     };
00236
00245     static unsigned long total_size(unsigned num)
00246     {
00247         static_assert(Desc_align >= Avail_align,
00248             "virtqueue alignment assumptions broken");
00249         return l4_round_size(desc_size(num) + avail_size(num), Used_align)
00250             + used_size(num);
00251     }
00252
00261     static unsigned long desc_size(unsigned num)
00262     { return num * 16; }
00263
00269     static unsigned long desc_align()
00270     { return Desc_align; }
00271
00279     static unsigned long avail_size(unsigned num)
00280     { return 2 * num + 6; }

```

```

00281
00287 static unsigned long avail_align()
00288 { return Avail_align; }
00289
00298 static unsigned long used_size(unsigned num)
00299 { return 8 * num + 6; }
00300
00306 static unsigned long used_align()
00307 { return Used_align; }
00308
00314 unsigned long total_size() const
00315 {
00316     return (reinterpret_cast<char *>(_used) - reinterpret_cast<char *>(_desc))
00317         + used_size(num());
00318 }
00319
00323 unsigned long avail_offset() const
00324 { return reinterpret_cast<char *>(_avail) - reinterpret_cast<char *>(_desc); }
00325
00329 unsigned long used_offset() const
00330 { return reinterpret_cast<char *>(_used) - reinterpret_cast<char *>(_desc); }
00331
00349 void setup(unsigned num, void *desc, void *avail, void *used)
00350 {
00351     if (num > 0x10000)
00352         throw L4::Runtime_error(-L4_EINVAL, "Queue too large.");
00353
00354     _idx_mask = num - 1;
00355     _desc = static_cast<Desc*>(desc);
00356     _avail = static_cast<Avail*>(avail);
00357     _used = static_cast<Used*>(used);
00358
00359     _current_avail = 0;
00360
00361     L4Re::Util::Dbg().printf("VQ[%p]: num=%d d:%p a:%p u:%p\n",
00362                             this, num, _desc, _avail, _used);
00363 }
00364
00378 void setup_simple(unsigned num, void *ring)
00379 {
00380     l4_addr_t desc = reinterpret_cast<l4_addr_t>(ring);
00381     l4_addr_t avail = l4_round_size(desc + desc_size(num), Avail_align);
00382     void *used = reinterpret_cast<void *>(
00383         l4_round_size(avail + avail_size(num), Used_align));
00384     setup(num, ring, reinterpret_cast<void *>(avail), used);
00385 }
00386
00392 void dump(Desc const *d) const
00393 { d->dump(d - _desc); }
00394
00400 bool ready() const
00401 { return L4_LIKELY(_desc != 0); }
00402
00404 unsigned num() const
00405 { return _idx_mask + 1; }
00406
00414 bool no_notify_guest() const
00415 {
00416     return _avail->flags.no_irq();
00417 }
00418
00426 bool no_notify_host() const
00427 {
00428     return _used->flags.no_notify();
00429 }
00430
00436 void no_notify_host(bool value)
00437 {
00438     _used->flags.no_notify() = value;
00439 }
00440
00449 l4_uint16_t get_avail_idx() const { return _avail->idx; }
00450
00456 l4_uint16_t get_tail_avail_idx() const { return _current_avail; }
00457 };
00458
00459 namespace Driver {
00461
00470 class Virtqueue : public L4virtio::Virtqueue
00471 {
00472 private:
00474     l4_uint16_t _next_free;
00475
00476 public:
00477     enum End_of_queue
00478     {

```


```

00479     // Indicates the end of the queue.
00480     Eoq = 0xFFFF
00481 };
00482
00483 Virtqueue() : _next_free(Eoq) {}
00484
00494 void initialize_rings(unsigned num)
00495 {
00496     _used->idx = 0;
00497     _avail->idx = 0;
00498
00499     // setup the freelist
00500     for (l4_uint16_t d = 0; d < num - 1; ++d)
00501         _desc[d].next = d + 1;
00502     _desc[num - 1].next = Eoq;
00503     _next_free = 0;
00504 }
00505
00522 void init_queue(unsigned num, void *desc, void *avail, void *used)
00523 {
00524     setup(num, desc, avail, used);
00525     initialize_rings(num);
00526 }
00527
00537 void init_queue(unsigned num, void *base)
00538 {
00539     setup_simple(num, base);
00540     initialize_rings(num);
00541 }
00542
00543
00558 l4_uint16_t alloc_descriptor()
00559 {
00560     l4_uint16_t idx = _next_free;
00561     if (idx == Eoq)
00562         return Eoq;
00563
00564     _next_free = _desc[idx].next;
00565
00566     return idx;
00567 }
00568
00574 void enqueue_descriptor(l4_uint16_t descno)
00575 {
00576     if (descno > _idx_mask)
00577         throw L4::Bounds_error();
00578
00579     _avail->ring[_avail->idx & _idx_mask] = descno; // _avail->idx expected to wrap
00580     wmb();
00581     ++_avail->idx;
00582 }
00583
00590 Desc &desc(l4_uint16_t descno)
00591 {
00592     if (descno > _idx_mask)
00593         throw L4::Bounds_error();
00594
00595     return _desc[descno];
00596 }
00597
00609 l4_uint16_t find_next_used(l4_uint32_t *len = nullptr)
00610 {
00611     if (_current_avail == _used->idx)
00612         return Eoq;
00613
00614     auto elem = _used->ring[_current_avail++ & _idx_mask];
00615
00616     if (len)
00617         *len = elem.len;
00618
00619     return elem.id;
00620 }
00621
00631 void free_descriptor(l4_uint16_t head, l4_uint16_t tail)
00632 {
00633     if (head > _idx_mask || tail > _idx_mask)
00634         throw L4::Bounds_error();
00635
00636     _desc[tail].next = _next_free;
00637     _next_free = head;
00638 }
00639 };
00640
00641 }
00642 } // namespace L4virtio

```

## 16.274 I4/libedid/edid.h File Reference

```
#include <l4/sys/compiler.h>  
Include dependency graph for edid.h:
```



### Enumerations

- enum [Libedid\\_consts](#) { [Libedid\\_block\\_size](#) = 128 }  
*EDID constants.*

### Functions

- int [libedid\\_check\\_header](#) (const unsigned char \*edid)  
*Check for valid EDID header.*
- int [libedid\\_checksum](#) (const unsigned char \*edid)  
*Calculates the EDID checksum.*
- unsigned [libedid\\_version](#) (const unsigned char \*edid)  
*Returns the EDID version number.*
- unsigned [libedid\\_revision](#) (const unsigned char \*edid)  
*Returns the EDID revision number.*
- void [libedid\\_pnp\\_id](#) (const unsigned char \*edid, unsigned char \*id)  
*Extracts the display's PnP ID.*
- void [libedid\\_preferred\\_resolution](#) (const unsigned char \*edid, unsigned \*w, unsigned \*h)  
*Extract the display's preferred mode.*
- unsigned [libedid\\_num\\_ext\\_blocks](#) (const unsigned char \*edid)  
*Get the number of EDID extension blocks.*
- unsigned [libedid\\_dump\\_standard\\_timings](#) (const unsigned char \*edid)  
*Dump the standard timings to stdout.*
- void [libedid\\_dump](#) (const unsigned char \*edid)  
*Dump raw EDID data to stdout.*

## 16.275 edid.h

[Go to the documentation of this file.](#)

```

00001
00004 /*
00005  * (c) 2014 Matthias Lange <matthias.lange@kernkonzept.com>
00006  *
00007  * This file is part of TUD:OS and distributed under the terms of the
00008  * GNU Lesser General Public License 2.1.
00009  * Please see the COPYING-LGPL-2.1 file for details.
00010  */
00011 #pragma once
00012
00013 #include <l4/sys/compiler.h>
00014
00019
00023 enum Libedid_consts
00024 {
00025     Libedid_block_size = 128,
00026 };
00027
00028 __BEGIN_DECLS
00029
00037 int libedid_check_header(const unsigned char *edid);
00038
00046 int libedid_checksum(const unsigned char *edid);
00047
00055 unsigned libedid_version(const unsigned char *edid);
00056
00064 unsigned libedid_revision(const unsigned char *edid);
00065
00072 void libedid_pnp_id(const unsigned char *edid, unsigned char *id);
00073
00081 void libedid_prefered_resolution(const unsigned char *edid,
00082                                 unsigned *w, unsigned *h);
00083
00091 unsigned libedid_num_ext_blocks(const unsigned char *edid);
00092
00100 unsigned libedid_dump_standard_timings(const unsigned char *edid);
00101
00107 void libedid_dump(const unsigned char *edid);
00108
00110
00111 __END_DECLS

```


## 16.276 l4/re/c/dataspace.h File Reference

Data space C interface.


```
#include <l4/sys/compiler.h>
```

```
#include <l4/sys/types.h>
```

Include dependency graph for dataspace.h:



This graph shows which files directly or indirectly include this file:



## Data Structures

- struct [l4re\\_ds\\_stats\\_t](#)  
*Information about the data space.*

## Enumerations

- enum [l4re\\_ds\\_map\\_flags](#) { }  
*Flags to specify the memory mapping type of a request.*

## Functions

- [l4\\_ret\\_t l4re\\_ds\\_clear](#) ([l4re\\_ds\\_t](#) ds, [l4re\\_ds\\_offset\\_t](#) offset, [l4re\\_ds\\_size\\_t](#) size) [L4\\_NOTHROW](#)  
*Clear parts of a dataspace.*
- [l4\\_ret\\_t l4re\\_ds\\_allocate](#) ([l4re\\_ds\\_t](#) ds, [l4re\\_ds\\_offset\\_t](#) offset, [l4re\\_ds\\_size\\_t](#) size) [L4\\_NOTHROW](#)  
*Allocate a range in the dataspace.*
- [l4\\_ret\\_t l4re\\_ds\\_copy\\_in](#) ([l4re\\_ds\\_t](#) ds, [l4re\\_ds\\_offset\\_t](#) dst\_offs, [l4re\\_ds\\_t](#) src, [l4re\\_ds\\_offset\\_t](#) src\_offs, [l4re\\_ds\\_size\\_t](#) size) [L4\\_NOTHROW](#)  
*Copy contents from another dataspace.*
- [l4re\\_ds\\_size\\_t l4re\\_ds\\_size](#) ([l4re\\_ds\\_t](#) ds) [L4\\_NOTHROW](#)  
*Get size of a dataspace.*
- [l4re\\_ds\\_flags\\_t l4re\\_ds\\_flags](#) ([l4re\\_ds\\_t](#) ds) [L4\\_NOTHROW](#)  
*Get flags of the dataspace.*
- [l4\\_ret\\_t l4re\\_ds\\_info](#) ([l4re\\_ds\\_t](#) ds, [l4re\\_ds\\_stats\\_t](#) \*stats) [L4\\_NOTHROW](#)  
*Get information on the dataspace.*
- [l4\\_ret\\_t l4re\\_ds\\_map\\_info](#) ([l4re\\_ds\\_t](#) ds, [l4\\_addr\\_t](#) \*start\_addr, [l4\\_addr\\_t](#) \*end\_addr) [L4\\_NOTHROW](#)  
*Get mapping range of dataspace.*

## Variables

- [L4\\_BEGIN\\_DECLS](#) typedef [l4\\_cap\\_idx\\_t](#) [l4re\\_ds\\_t](#)  
*Dataspace type.*



## 16.276.1 Detailed Description

Data space C interface.

Definition in file [dataspace.h](#).

## 16.277 dataspace.h

[Go to the documentation of this file.](#)

```

00001
00005 /*
00006  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00007  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00008  *      economic rights: Technische Universität Dresden (Germany)
00009  *
00010  * License: see LICENSE.spdx (in this directory or the directories above)
00011  */
00012 #pragma once
00013
00019
00020 #include <14/sys/compiler.h>
00021 #include <14/sys/types.h>
00022
00023 L4_BEGIN_DECLS
00024
00029 typedef l4_cap_idx_t l4re_ds_t;
00030 typedef l4_uint64_t l4re_ds_size_t;
00031 typedef l4_uint64_t l4re_ds_offset_t;
00032 typedef l4_uint64_t l4re_ds_map_addr_t;
00033 typedef unsigned long l4re_ds_flags_t;
00034
00039 typedef struct {
00040     l4re_ds_size_t size;
00041     l4re_ds_flags_t flags;
00042 } l4re_ds_stats_t;
00043
00048 enum l4re_ds_map_flags {
00049     L4RE_DS_F_R    = L4_FPAGE_RO,
00050     L4RE_DS_F_W    = L4_FPAGE_W,
00051     L4RE_DS_F_X    = L4_FPAGE_X,
00052     L4RE_DS_F_RW   = L4_FPAGE_RW,
00053     L4RE_DS_F_RX   = L4_FPAGE_RX,
00054     L4RE_DS_F_RWX  = L4_FPAGE_RWX,
00055
00056     L4RE_DS_F_RIGHTS_MASK = 0x0f,
00057
00058     L4RE_DS_F_NORMAL      = 0x00,
00059     L4RE_DS_F_CACHEABLE  = L4RE_DS_F_NORMAL,
00060     L4RE_DS_F_BUFFERABLE = 0x10,
00061     L4RE_DS_F_UNCACHEABLE = 0x20,
00062     L4RE_DS_F_CACHING_MASK = 0x30,
00063     L4RE_DS_F_CACHING_SHIFT = 4,
00064 };
00065
00071 L4_CV l4_ret_t
00072 l4re_ds_map(l4re_ds_t ds,
00073             l4re_ds_offset_t offset,
00074             l4re_ds_flags_t flags,
00075             l4re_ds_map_addr_t local_addr,
00076             l4re_ds_map_addr_t min_addr,
00077             l4re_ds_map_addr_t max_addr) L4_NOTHROW;
00078
00084 L4_CV l4_ret_t
00085 l4re_ds_map_region(l4re_ds_t ds,
00086                   l4re_ds_offset_t offset,
00087                   l4re_ds_flags_t flags,
00088                   l4re_ds_map_addr_t min_addr,
00089                   l4re_ds_map_addr_t max_addr) L4_NOTHROW;
00090
00097 L4_CV l4_ret_t
00098 l4re_ds_clear(l4re_ds_t ds, l4re_ds_offset_t offset,
00099              l4re_ds_size_t size) L4_NOTHROW;
00100
00107 L4_CV l4_ret_t
00108 l4re_ds_allocate(l4re_ds_t ds,
00109                 l4re_ds_offset_t offset,
00110                 l4re_ds_size_t size) L4_NOTHROW;
00111

```

```

00118 L4_CV l4_ret_t
00119 l4re_ds_copy_in(l4re_ds_t ds, l4re_ds_offset_t dst_offs,
00120                 l4re_ds_t src, l4re_ds_offset_t src_offs,
00121                 l4re_ds_size_t size) L4_NOTHROW;
00122
00129 L4_CV l4re_ds_size_t
00130 l4re_ds_size(l4re_ds_t ds) L4_NOTHROW;
00131
00138 L4_CV l4re_ds_flags_t
00139 l4re_ds_flags(l4re_ds_t ds) L4_NOTHROW;
00140
00147 L4_CV l4_ret_t
00148 l4re_ds_info(l4re_ds_t ds, l4re_ds_stats_t *stats) L4_NOTHROW;
00149
00156 L4_CV l4_ret_t
00157 l4re_ds_map_info(l4re_ds_t ds,
00158                 l4_addr_t *start_addr, l4_addr_t *end_addr) L4_NOTHROW;
00159
00160 L4_END_DECLS

```

## 16.278 l4/re/c/dma\_space.h File Reference


DMA space C interface.

```

#include <l4/sys/compiler.h>
#include <l4/sys/types.h>
#include <l4/re/c/dataspace.h>

```

Include dependency graph for dma\_space.h:



### Typedefs

- typedef `l4_cap_idx_t l4re_dma_space_t`  
DMA space capability type.
- typedef `l4_uint64_t l4re_dma_space_dma_addr_t`  
Data type for DMA addresses.

## Enumerations

- enum [l4re\\_dma\\_space\\_direction](#) { [L4RE\\_DMA\\_SPACE\\_BIDIRECTIONAL](#) , [L4RE\\_DMA\\_SPACE\\_TO\\_DEVICE](#) , [L4RE\\_DMA\\_SPACE\\_FROM\\_DEVICE](#) , [L4RE\\_DMA\\_SPACE\\_NONE](#) }  
*Direction of the DMA transfers.*
- enum [l4re\\_dma\\_space\\_space\\_attrbs](#) { [L4RE\\_DMA\\_SPACE\\_COHERENT](#) = 1 << 0 , [L4RE\\_DMA\\_SPACE\\_PHYS\\_SPACE](#) = 1 << 1 }  
*Attributes assigned to the DMA space when associated with a specific device.*

## Functions

- [l4\\_ret\\_t l4re\\_dma\\_space\\_map](#) ([l4re\\_dma\\_space\\_t](#) dma, [l4re\\_ds\\_t](#) src, [l4re\\_ds\\_offset\\_t](#) offset, [l4\\_size\\_t](#) \*size, unsigned long attrs, enum [l4re\\_dma\\_space\\_direction](#) dir, [l4re\\_dma\\_space\\_dma\\_addr\\_t](#) \*dma\_addr) [L4\\_NOTHROW](#)  
*Map the given part of this data space into the DMA address space.*
- [l4\\_ret\\_t l4re\\_dma\\_space\\_unmap](#) ([l4re\\_dma\\_space\\_t](#) dma, [l4re\\_dma\\_space\\_dma\\_addr\\_t](#) dma\_addr, [l4\\_size\\_t](#) size, unsigned long attrs, enum [l4re\\_dma\\_space\\_direction](#) dir) [L4\\_NOTHROW](#)  
*Unmap the given part of this data space from the DMA address space.*
- [l4\\_ret\\_t l4re\\_dma\\_space\\_associate](#) ([l4re\\_dma\\_space\\_t](#) dma, [l4\\_cap\\_idx\\_t](#) dma\_task, unsigned long attr) [L4\\_NOTHROW](#)  
*Associate a (kernel) DMA space for a device to this Dma\_space.*
- [l4\\_ret\\_t l4re\\_dma\\_space\\_disassociate](#) ([l4re\\_dma\\_space\\_t](#) dma)  
*Disassociate the (kernel) DMA space from this Dma\_space.*

## 16.278.1 Detailed Description

DMA space C interface.

Definition in file [dma\\_space.h](#).

## 16.278.2 Enumeration Type Documentation

### 16.278.2.1 l4re\_dma\_space\_direction

enum [l4re\\_dma\\_space\\_direction](#)

Direction of the DMA transfers.

#### Enumerator

<a href="#">L4RE_DMA_SPACE_BIDIRECTIONAL</a>	device reads and writes to the memory
<a href="#">L4RE_DMA_SPACE_TO_DEVICE</a>	device reads the memory
<a href="#">L4RE_DMA_SPACE_FROM_DEVICE</a>	device writes to the memory
<a href="#">L4RE_DMA_SPACE_NONE</a>	device is coherently connected

Definition at line 27 of file [dma\\_space.h](#).

### 16.278.2.2 l4re\_dma\_space\_space\_attribs

enum `l4re_dma_space_space_attribs`

Attributes assigned to the DMA space when associated with a specific device.

See also

`Space_attribs`

#### Enumerator

L4RE_DMA_SPACE_COHERENT	The device is connected coherently with the cache. This means that the <code>map()</code> and <code>unmap()</code> do not need to sync CPU caches before and after DMA.
L4RE_DMA_SPACE_PHYS_SPACE	The DMA space has no DMA task assigned and uses the CPUs physical memory.

Definition at line 38 of file [dma\\_space.h](#).

## 16.279 dma\_space.h

[Go to the documentation of this file.](#)

```

00001
00005 /*
00006  * (c) 2014 Alexander Warg <alexander.warg@kernkonzept.com>
00007  *
00008  * License: see LICENSE.spdx (in this directory or the directories above)
00009  */
00010 #pragma once
00011
00017
00018 #include <l4/sys/compiler.h>
00019 #include <l4/sys/types.h>
00020 #include <l4/re/c/dataspace.h>
00021
00022 L4_BEGIN_DECLS
00023
00027 enum l4re_dma_space_direction
00028 {
00029     L4RE_DMA_SPACE_BIDIRECTIONAL,
00030     L4RE_DMA_SPACE_TO_DEVICE,
00031     L4RE_DMA_SPACE_FROM_DEVICE,
00032     L4RE_DMA_SPACE_NONE
00033 };
00034
00038 enum l4re_dma_space_space_attribs
00039 {
00040     L4RE_DMA_SPACE_COHERENT = 1 << 0,
00041     L4RE_DMA_SPACE_PHYS_SPACE = 1 << 1,
00042 };
00043
00049 typedef l4_cap_idx_t l4re_dma_space_t;
00050
00052 typedef l4_uint64_t l4re_dma_space_dma_addr_t;
00053
00060 L4_CV l4_ret_t
00061 l4re_dma_space_map(l4re_dma_space_t dma, l4re_ds_t src,
00062                   l4re_ds_offset_t offset,
00063                   l4_size_t * size, unsigned long attrs,
00064                   enum l4re_dma_space_direction dir,
00065                   l4re_dma_space_dma_addr_t *dma_addr) L4_NOTHROW;
00066
00067
00074 L4_CV l4_ret_t
00075 l4re_dma_space_unmap(l4re_dma_space_t dma, l4re_dma_space_dma_addr_t dma_addr,
00076                    l4_size_t size, unsigned long attrs,
00077                    enum l4re_dma_space_direction dir) L4_NOTHROW;

```

```

00078
00085 L4_CV l4_ret_t
00086 l4re_dma_space_associate(l4re_dma_space_t dma, l4_cap_idx_t dma_task,
00087                             unsigned long attr) L4_NOTHROW;
00088
00095 L4_CV l4_ret_t
00096 l4re_dma_space_disassociate(l4re_dma_space_t dma);
00097
00098
00099 L4_END_DECLS

```

## 16.280 l4/re/c/event.h File Reference


Event C interface.

```


#include <l4/sys/compiler.h>
#include <l4/sys/types.h>
#include <l4/re/c/dataspace.h>
#include <l4/re/event.h>

```

Include dependency graph for event.h:



This graph shows which files directly or indirectly include this file:



## Data Structures

- struct [l4re\\_event\\_t](#)  
*Event structure used in buffer.*

## Functions

- [l4\\_ret\\_t l4re\\_event\\_get\\_buffer](#) (const [l4\\_cap\\_idx\\_t](#) server, const [l4re\\_ds\\_t](#) ds) [L4\\_NOTHROW](#)  
*Get an event signal buffer.*
- [l4\\_ret\\_t l4re\\_event\\_get\\_num\\_streams](#) (const [l4\\_cap\\_idx\\_t](#) server) [L4\\_NOTHROW](#)  
*Get number of streams.*
- [l4\\_ret\\_t l4re\\_event\\_get\\_stream\\_info](#) (const [l4\\_cap\\_idx\\_t](#) server, int idx, [l4re\\_event\\_stream\\_info\\_t](#) \*info) [L4\\_NOTHROW](#)  
*Get information on a stream.*
- [l4\\_ret\\_t l4re\\_event\\_get\\_stream\\_info\\_for\\_id](#) (const [l4\\_cap\\_idx\\_t](#) server, [l4\\_umword\\_t](#) stream\_id, [l4re\\_event\\_stream\\_info\\_t](#) \*info) [L4\\_NOTHROW](#)  
*Get info for a stream given a stream id.*
- [l4\\_ret\\_t l4re\\_event\\_get\\_axis\\_info](#) (const [l4\\_cap\\_idx\\_t](#) server, [l4\\_umword\\_t](#) id, unsigned naxes, unsigned const \*axis, [l4re\\_event\\_absinfo\\_t](#) \*info) [L4\\_NOTHROW](#)  
*Get Axis information for a stream.*

## 16.280.1 Detailed Description

Event C interface.

Definition in file [event.h](#).

## 16.281 event.h

[Go to the documentation of this file.](#)

```

00001
00005 /*
00006  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00007  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00008  *      economic rights: Technische Universität Dresden (Germany)
00009  *
00010  * License: see LICENSE.spdx (in this directory or the directories above)
00011  */
00012 #pragma once
00013
00019
00020 #include <l4/sys/compiler.h>
00021 #include <l4/sys/types.h>
00022 #include <l4/re/c/dataspace.h>
00023 #include <l4/re/event.h>
00024
00025 L4_BEGIN_DECLS
00026
00030 typedef struct
00031 {
00032     long long time;
00033     unsigned short type;
00034     unsigned short code;
00035     int value;
00036     l4_umword_t stream_id;
00037 } l4re_event_t;
00038
00050 L4_CV l4_ret_t
00051 l4re_event_get_buffer(const l4_cap_idx_t server,
00052                      const l4re_ds_t ds) L4_NOTHROW;
00053

```

```

00064 L4_CV l4_ret_t
00065 l4re_event_get_num_streams(const l4_cap_idx_t server) L4_NOTHROW;
00066
00079 L4_CV l4_ret_t
00080 l4re_event_get_stream_info(const l4_cap_idx_t server,
00081                             int idx, l4re_event_stream_info_t *info) L4_NOTHROW;
00082
00095 L4_CV l4_ret_t
00096 l4re_event_get_stream_info_for_id(const l4_cap_idx_t server,
00097                                    l4_umword_t stream_id,
00098                                    l4re_event_stream_info_t *info) L4_NOTHROW;
00099
00115 L4_CV l4_ret_t
00116 l4re_event_get_axis_info(const l4_cap_idx_t server, l4_umword_t id,
00117                           unsigned naxes, unsigned const *axis,
00118                           l4re_event_absinfo_t *info) L4_NOTHROW;
00119
00120 L4_END_DECLS

```


## 16.282 l4/re/event.h File Reference

Events.


```
#include <l4/sys/compiler.h>
```

```
#include <l4/sys/l4int.h>
```

Include dependency graph for event.h:



This graph shows which files directly or indirectly include this file:



## 16.282.1 Detailed Description

Events.

Definition in file [event.h](#).

## 16.283 event.h

[Go to the documentation of this file.](#)

```

00001
00005 /*
00006  * (c) 2009 Alexander Warg <warg@os.inf.tu-dresden.de>
00007  *      economic rights: Technische Universität Dresden (Germany)
00008  *
00009  * License: see LICENSE.spdx (in this directory or the directories above)
00010  */
00011 #pragma once
00012
00013 #include <14/sys/compiler.h>
00014 #include <14/sys/14int.h>
00015
00016 typedef struct L4_EXPORT_TYPE l4re_event_stream_id_t
00017 {
00018     l4_uint16_t bustype;
00019     l4_uint16_t vendor;
00020     l4_uint16_t product;
00021     l4_uint16_t version;
00022 } l4re_event_stream_id_t;
00023
00024 typedef struct L4_EXPORT_TYPE l4re_event_absinfo_t
00025 {
00026     l4_int32_t value;
00027     l4_int32_t min;
00028     l4_int32_t max;
00029     l4_int32_t fuzz;
00030     l4_int32_t flat;
00031     l4_int32_t resolution;
00032 } l4re_event_absinfo_t;
00033
00034 enum l4re_event_stream_max_values_t
00035 {
00036     L4RE_EVENT_EV_MAX = 0x1f,
00037     L4RE_EVENT_KEY_MAX = 0x1ff,
00038     L4RE_EVENT_REL_MAX = 0xf,
00039     L4RE_EVENT_ABS_MAX = 0x3f,
00040     L4RE_EVENT_PROP_MAX = 0x1f,
00041     L4RE_EVENT_SW_MAX = 0xf, // should be >= L4RE_SW_MAX
00042 };
00043
00044 enum l4re_event_stream_props_t
00045 {
00046     L4RE_EVENT_STREAM_CALIBRATE = 0x001,
00047 };
00048
00049
00050 #define __UNUM_B(x) ((x+1) + sizeof(unsigned long)*8 - 1) / (sizeof(unsigned long)*8)
00051
00052 typedef struct L4_EXPORT_TYPE l4re_event_stream_info_t
00053 {
00054     l4_umword_t stream_id;
00055     char name[32];
00056     char phys[32];
00057     l4re_event_stream_id_t id;
00058
00059     unsigned long propbits[__UNUM_B(L4RE_EVENT_PROP_MAX)];
00060
00061     unsigned long evbits[__UNUM_B(L4RE_EVENT_EV_MAX)];
00062     unsigned long keybits[__UNUM_B(L4RE_EVENT_KEY_MAX)];
00063     unsigned long relbits[__UNUM_B(L4RE_EVENT_REL_MAX)];
00064     unsigned long absbits[__UNUM_B(L4RE_EVENT_ABS_MAX)];
00065     unsigned long swbits[__UNUM_B(L4RE_EVENT_SW_MAX)];
00066 } l4re_event_stream_info_t;
00067
00068
00069 typedef struct L4_EXPORT_TYPE l4re_event_stream_state_t
00070 {
00071     unsigned long keybits[__UNUM_B(L4RE_EVENT_KEY_MAX)];
00072     unsigned long swbits[__UNUM_B(L4RE_EVENT_SW_MAX)];
00073 } l4re_event_stream_state_t;
00074
00075 #undef __UNUM_B
00076

```



## 16.284 event\_buffer.h

```

00001 #pragma once
00002 /*
00003  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>
00004  *      economic rights: Technische Universität Dresden (Germany)
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00008
00009 #include <l4/sys/compiler.h>
00010 #include <l4/sys/linkage.h>
00011 #include <l4/re/c/event.h>
00012
00013 L4_BEGIN_DECLS
00014
00015 typedef struct l4re_event_buffer_consumer_t
00016 {
00017     unsigned long _obj_buf[8];
00018 } l4re_event_buffer_consumer_t;
00019
00020 L4_CV void
00021 l4re_event_free(l4re_event_t *e) L4_NOTHROW;
00022
00023 L4_CV l4_ret_t
00024 l4re_event_buffer_attach(l4re_event_buffer_consumer_t *evbuf,
00025                          l4re_ds_t ds, l4_cap_idx_t rm) L4_NOTHROW;
00026
00027 L4_CV l4_ret_t
00028 l4re_event_buffer_detach(l4re_event_buffer_consumer_t *evbuf,
00029                          l4_cap_idx_t rm) L4_NOTHROW;
00030
00031 L4_CV l4re_event_t *
00032 l4re_event_buffer_next(l4re_event_buffer_consumer_t *evbuf) L4_NOTHROW;
00033
00034 typedef L4_CV void l4re_event_buffer_cb_t(l4re_event_t *ev, void *data);
00035
00036 L4_CV void
00037 l4re_event_buffer_consumer_foreach_available_event(l4re_event_buffer_consumer_t *evbuf,
00038                                                    void *data, l4re_event_buffer_cb_t *cb);
00039
00040
00041 L4_CV void
00042 l4re_event_buffer_consumer_process(l4re_event_buffer_consumer_t *evbuf,
00043                                    l4_cap_idx_t irq, l4_cap_idx_t thread, void *data,
00044                                    l4re_event_buffer_cb_t *cb);
00045
00046 L4_END_DECLS

```

## 16.285 l4/re/c/inhibitor.h File Reference


Inhibitor C interface.

```

#include <l4/sys/compiler.h>
#include <l4/sys/types.h>

```

Include dependency graph for inhibitor.h:



## Functions

- [L4\\_BEGIN\\_DECLS l4\\_ret\\_t l4re\\_inhibitor\\_acquire](#) ([l4\\_cap\\_idx\\_t](#) cap, [l4\\_umword\\_t](#) id, char const \*reason)  
*Acquire an inhibitor lock.*
- [l4\\_ret\\_t l4re\\_inhibitor\\_release](#) ([l4\\_cap\\_idx\\_t](#) cap, [l4\\_umword\\_t](#) id)  
*Release an inhibitor lock.*
- [l4\\_ret\\_t l4re\\_inhibitor\\_next\\_lock\\_info](#) ([l4\\_cap\\_idx\\_t](#) cap, char \*name, unsigned len, [l4\\_mword\\_t](#) current\_id)  
*Get information for the next available inhibitor lock.*

## 16.285.1 Detailed Description

Inhibitor C interface.

Definition in file [inhibitor.h](#).

## 16.285.2 Function Documentation

### 16.285.2.1 l4re\_inhibitor\_acquire()

```

L4_BEGIN_DECLS l4_ret_t l4re_inhibitor_acquire (
    l4_cap_idx_t cap,
    l4_umword_t id,
    char const * reason)

```

Acquire an inhibitor lock.

#### Parameters

<i>cap</i>	Capability for the Inhibitor object (see <a href="#">L4Re::Inhibitor</a> )
------------	--

<i>id</i>	ID of the inhibitor lock that shall be acquired.
<i>reason</i>	Reason why the inhibitor lock is acquired. (Used for informing the user or debugging.)

**Returns**

0 for success, <0 on error.

**See also**

[L4Re::Inhibitor::acquire\(\)](#).

References [L4\\_CV](#), and [L4\\_EXPORT](#).

**16.285.2.2 l4re\_inhibitor\_next\_lock\_info()**

```
l4_ret_t l4re_inhibitor_next_lock_info (
    l4_cap_idx_t cap,
    char * name,
    unsigned len,
    l4_mword_t current_id)
```

Get information for the next available inhibitor lock.

**Parameters**

<i>cap</i>	Capability to the Inhibitor object (see <a href="#">L4Re::Inhibitor</a> )
<i>name</i>	A pointer to a buffer for the name of the lock.
<i>len</i>	The length of the available buffer (usually <a href="#">L4Re::Inhibitor::Name_max</a> is used).
<i>current_id</i>	The ID of the last available lock, use -1 to get the first lock.

**Return values**

>0	The ID of the next available lock if there is one (in this case name shall contain the name of the inhibitor lock).
-L4_ENODEV	if there are no more locks.
<0	Any other negative failure value.

**See also**

[L4Re::Inhibitor::next\\_lock\\_info\(\)](#).

References [L4\\_END\\_DECLS](#).

### 16.285.2.3 l4re\_inhibitor\_release()

```
l4_ret_t l4re_inhibitor_release (
    l4_cap_idx_t cap,
    l4_umword_t id)
```

Release an inhibitor lock.

#### Parameters

<i>cap</i>	Capability for the Inhibitor object (see <a href="#">L4Re::Inhibitor</a> ).
<i>id</i>	ID of inhibitor that shall be released.

#### Returns

0 for success, <0 on error.

#### See also

[L4Re::Inhibitor::release\(\)](#).

References [L4\\_CV](#), and [L4\\_EXPORT](#).

## 16.286 inhibitor.h


[Go to the documentation of this file.](#)

```
00001 /*
00002  * (c) 2014 Steffen Liebergeld <steffen.liebergeld@kernkonzept.com>
00003  *
00004  * License: see LICENSE.spdx (in this directory or the directories above)
00005  */
00006 #pragma once
00007
00013 #include <l4/sys/compiler.h>
00014 #include <l4/sys/types.h>
00015
00016 L4_BEGIN_DECLS
00017
00028 L4_CV l4_ret_t L4_EXPORT
00029 l4re_inhibitor_acquire(l4_cap_idx_t cap, l4_umword_t id,
00030                       char const *reason);
00031
00039 L4_CV l4_ret_t L4_EXPORT
00040 l4re_inhibitor_release(l4_cap_idx_t cap, l4_umword_t id);
00041
00057 L4_CV l4_ret_t L4_EXPORT
00058 l4re_inhibitor_next_lock_info(l4_cap_idx_t cap, char *name,
00059                               unsigned len, l4_mword_t current_id);
00060
00061 L4_END_DECLS
00062
```

## 16.287 l4/re/c/log.h File Reference

Log C interface.

```
#include <l4/re/env.h>
#include <l4/sys/compiler.h>
Include dependency graph for log.h:
```



### Functions

- [L4\\_BEGIN\\_DECLS](#) void [l4re\\_log\\_print](#) (char const \*string) [L4\\_NOTHROW](#)  
Write a null terminated string to the default log.
- void [l4re\\_log\\_printn](#) (char const \*string, int len) [L4\\_NOTHROW](#)  
Write a string of a given length to the default log.
- void [l4re\\_log\\_print\\_srv](#) (const [l4\\_cap\\_idx\\_t](#) logcap, char const \*string) [L4\\_NOTHROW](#)  
Write a null terminated string to a log.
- void [l4re\\_log\\_printn\\_srv](#) (const [l4\\_cap\\_idx\\_t](#) logcap, char const \*string, int len) [L4\\_NOTHROW](#)  
Write a string of a given length to a log.

### 16.287.1 Detailed Description

Log C interface.

Definition in file [log.h](#).

## 16.288 log.h

[Go to the documentation of this file.](#)

```
00001
00005 /*
00006  * (c) 2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>
00007  *     economic rights: Technische Universität Dresden (Germany)
00008  *
00009  * License: see LICENSE.spdx (in this directory or the directories above)
00010  */
00011 #pragma once
00012
```

```

00018
00019 #include <l4/re/env.h>
00020 #include <l4/sys/compiler.h>
00021
00022 L4_BEGIN_DECLS
00023
00032 L4_CV L4_INLINE void
00033 l4re_log_print(char const *string) L4_NOTHROW;
00034
00044 L4_CV L4_INLINE void
00045 l4re_log_printn(char const *string, int len) L4_NOTHROW;
00046
00047
00048
00049
00059 L4_CV void
00060 l4re_log_print_srv(const l4_cap_idx_t logcap,
00061                  char const *string) L4_NOTHROW;
00062
00073 L4_CV void
00074 l4re_log_printn_srv(const l4_cap_idx_t logcap,
00075                   char const *string, int len) L4_NOTHROW;
00076
00077
00078 /***** Implementations *****/
00079
00080 L4_CV L4_INLINE void
00081 l4re_log_print(char const *string) L4_NOTHROW
00082 {
00083     l4re_log_print_srv(l4re_global_env->log, string);
00084 }
00085
00086 L4_CV L4_INLINE void
00087 l4re_log_printn(char const *string, int len) L4_NOTHROW
00088 {
00089     l4re_log_printn_srv(l4re_global_env->log, string, len);
00090 }
00091
00092 L4_END_DECLS

```

## 16.289 l4/re/c/mem\_alloc.h File Reference


Memory allocator C interface.

```

#include <l4/re/env.h>
#include <l4/sys/compiler.h>
#include <l4/sys/consts.h>
#include <l4/re/c/dataspace.h>

```

Include dependency graph for mem\_alloc.h:



### Enumerations

- enum [l4re\\_ma\\_flags](#)  
Flags for requesting memory at the memory allocator.

## Functions

- [l4\\_ret\\_t l4re\\_ma\\_alloc](#) (long size, [l4re\\_ds\\_t](#) const mem, unsigned long flags) [L4\\_NOTHROW](#)  
*Allocate memory.*
- [l4\\_ret\\_t l4re\\_ma\\_alloc\\_align](#) (long size, [l4re\\_ds\\_t](#) const mem, unsigned long flags, unsigned long align) [L4\\_NOTHROW](#)  
*Allocate memory.*
- [l4\\_ret\\_t l4re\\_ma\\_alloc\\_align\\_srv](#) ([l4\\_cap\\_idx\\_t](#) srv, long size, [l4re\\_ds\\_t](#) const mem, unsigned long flags, unsigned long align) [L4\\_NOTHROW](#)  
*Allocate memory.*

## 16.289.1 Detailed Description

Memory allocator C interface.

Definition in file [mem\\_alloc.h](#).

## 16.290 mem\_alloc.h

[Go to the documentation of this file.](#)

```

00001
00005 /*
00006  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>
00007  *      economic rights: Technische Universität Dresden (Germany)
00008  *
00009  * License: see LICENSE.spdx (in this directory or the directories above)
00010  */
00011 #pragma once
00012
00013 #include <l4/re/env.h>
00014 #include <l4/sys/compiler.h>
00015 #include <l4/sys/consts.h>
00016
00017 #include <l4/re/c/dataspace.h>
00018
00024
00025 L4_BEGIN_DECLS
00026
00032 enum l4re_ma_flags {
00033     L4RE_MA_CONTINUOUS = 0x01,
00034     L4RE_MA_PINNED     = 0x02,
00035     L4RE_MA_SUPER_PAGES = 0x04,
00036 };
00037
00038
00069 L4_CV L4_INLINE l4_ret_t
00070 l4re_ma_alloc(long size, l4re_ds_t const mem,
00071              unsigned long flags) L4_NOTHROW;
00072
00106 L4_CV L4_INLINE l4_ret_t
00107 l4re_ma_alloc_align(long size, l4re_ds_t const mem,
00108                    unsigned long flags, unsigned long align) L4_NOTHROW;
00109
00128 L4_CV l4_ret_t
00129 l4re_ma_alloc_align_srv(l4_cap_idx_t srv, long size,
00130                        l4re_ds_t const mem, unsigned long flags,
00131                        unsigned long align) L4_NOTHROW;
00132
00133 /***** Implementation *****/
00134
00135 L4_CV L4_INLINE l4_ret_t
00136 l4re_ma_alloc(long size, l4re_ds_t const mem,
00137              unsigned long flags) L4_NOTHROW
00138 {
00139     return l4re_ma_alloc_align_srv(l4re_global_env->mem_alloc, size, mem,
00140                                   flags, 0);
00141 }
00142
00143 L4_CV L4_INLINE l4_ret_t

```

```

00144 l4re_ma_alloc_align(long size, l4re_ds_t const mem,
00145                      unsigned long flags, unsigned long align) L4_NOTHROW
00146 {
00147     return l4re_ma_alloc_align_srv(l4re_global_env->mem_alloc, size, mem,
00148                                   flags, align);
00149 }
00150
00151 L4_END_DECLS

```

## 16.291 l4/re/c/namespace.h File Reference


Namespace functions, C interface.

```

#include <l4/re/env.h>
#include <l4/sys/compiler.h>

```

Include dependency graph for namespace.h:



### Enumerations

- enum [l4re\\_ns\\_register\\_flags](#)  
Namespace register flags.

### Functions

- [l4\\_ret\\_t l4re\\_ns\\_query\\_to\\_srv](#) ([l4re\\_namespace\\_t](#) srv, char const \*name, [l4\\_cap\\_idx\\_t](#) const cap, int timeout) [L4\\_NOTHROW](#)  
Query the name space for the object named by *name*.
- [l4\\_ret\\_t l4re\\_ns\\_query\\_srv](#) ([l4re\\_namespace\\_t](#) srv, char const \*name, [l4\\_cap\\_idx\\_t](#) const cap) [L4\\_NOTHROW](#)  
Query the name space for the object named by *name*.
- [l4\\_ret\\_t l4re\\_ns\\_register\\_obj\\_srv](#) ([l4re\\_namespace\\_t](#) srv, char const \*name, [l4\\_cap\\_idx\\_t](#) const obj, unsigned flags) [L4\\_NOTHROW](#)  
Register an object with a name.

### Variables

- [L4\\_BEGIN\\_DECLS](#) typedef [l4\\_cap\\_idx\\_t](#) [l4re\\_namespace\\_t](#)  
Namespace type.



## 16.291.1 Detailed Description

Namespace functions, C interface.

Definition in file [namespace.h](#).

## 16.292 namespace.h

[Go to the documentation of this file.](#)

```


00001
00005 /*
00006  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00007  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00008  *      economic rights: Technische Universität Dresden (Germany)
00009  *
00010  * License: see LICENSE.spdx (in this directory or the directories above)
00011  */
00012 #pragma once
00013
00019
00020 #include <l4/re/env.h>
00021 #include <l4/sys/compiler.h>
00022
00029 enum l4re_ns_register_flags {
00030     L4RE_NS_REGISTER_RO    = L4_FPAGE_RO,
00031     L4RE_NS_REGISTER_DIR  = 0x10,
00032     L4RE_NS_REGISTER_RW   = L4_FPAGE_RX,
00033     L4RE_NS_REGISTER_RWS  = L4_FPAGE_RWX,
00034     L4RE_NS_REGISTER_S    = L4_FPAGE_W,
00035 };
00036
00037 L4_BEGIN_DECLS
00038
00043 typedef l4_cap_idx_t l4re_namespace_t;
00044
00045
00046
00055 L4_CV l4_ret_t
00056 l4re_ns_query_to_srv(l4re_namespace_t srv, char const *name,
00057                     l4_cap_idx_t const cap, int timeout) L4_NOTHROW;
00058
00075 L4_CV L4_INLINE l4_ret_t
00076 l4re_ns_query_srv(l4re_namespace_t srv, char const *name,
00077                  l4_cap_idx_t const cap) L4_NOTHROW;
00078
00086 L4_CV l4_ret_t
00087 l4re_ns_register_obj_srv(l4re_namespace_t srv, char const *name,
00088                          l4_cap_idx_t const obj, unsigned flags) L4_NOTHROW;
00089
00090
00091
00092 /***** Implementation *****/
00093
00094 L4_CV L4_INLINE l4_ret_t
00095 l4re_ns_query_srv(l4re_namespace_t srv, char const *name,
00096                  l4_cap_idx_t const cap) L4_NOTHROW
00097 {
00098     return l4re_ns_query_to_srv(srv, name, cap, 40000);
00099 }
00100
00101
00102 L4_END_DECLS

```

## 16.293 l4/re/c/parent.h File Reference

Parent C interface.

```
#include <l4/sys/compiler.h>
#include <l4/sys/types.h>
Include dependency graph for parent.h:
```



## Functions

- [L4\\_BEGIN\\_DECLS](#) long [l4re\\_parent\\_signal](#) ([l4\\_cap\\_idx\\_t](#) parent, unsigned long sig, unsigned long val)  
*Send a signal using the parent protocol.*

### 16.293.1 Detailed Description

Parent C interface.

Definition in file [parent.h](#).

### 16.293.2 Function Documentation

#### 16.293.2.1 l4re\_parent\_signal()

```
L4\_BEGIN\_DECLS long l4re_parent_signal (
    l4\_cap\_idx\_t parent,
    unsigned long sig,
    unsigned long val)
```

Send a signal using the parent protocol.

#### Parameters

<i>parent</i>	Capability index of parent to send signal to.
<i>sig</i>	Signal to send
<i>val</i>	Value of the signal

## Return values

0	Success
<0	IPC error

## See also

[L4Re::Parent::signal](#)

References [L4\\_END\\_DECLS](#).

## 16.294 parent.h

[Go to the documentation of this file.](#)

```

00001 /*
00002  * Copyright (C) 2024-2025 Kernkonzept GmbH.
00003  * Author(s): Marcus Haehnel <marcus.haehnel@kernkonzept.com>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007
00012
00013 #pragma once
00014
00019
00020 #include <l4/sys/compiler.h>
00021 #include <l4/sys/types.h>
00022
00023 L4_BEGIN_DECLS
00024
00037 L4_CV long L4_EXPORT
00038 l4re_parent_signal(l4_cap_idx_t parent, unsigned long sig, unsigned long val);
00039
00040 L4_END_DECLS

```

## 16.295 I4/re/c/rm.h File Reference


Region map interface, C interface.

```

#include <l4/re/env.h>
#include <l4/re/c/dataspace.h>
#include <l4/sys/compiler.h>

```

Include dependency graph for rm.h:



## Enumerations

- enum `l4re_rm_flags_values` {  
`L4RE_RM_F_R` = `L4RE_DS_F_R` , `L4RE_RM_F_W` = `L4RE_DS_F_W` , `L4RE_RM_F_X` = `L4RE_DS_F_X`  
, `L4RE_RM_F_RX` = `L4RE_DS_F_RX` ,  
`L4RE_RM_F_RW` = `L4RE_DS_F_RW` , `L4RE_RM_F_RWX` = `L4RE_DS_F_RWX` , `L4RE_RM_F_KERNEL`  
= `0x100` , `L4RE_RM_F_DETACH_FREE` = `0x200` ,  
`L4RE_RM_F_PAGER` = `0x400` , `L4RE_RM_F_RESERVED` = `0x800` , `L4RE_RM_CACHING_SHIFT` = `4` ,  
`L4RE_RM_F_CACHING` = `L4RE_DS_F_CACHING_MASK` ,  
`L4RE_RM_REGION_FLAGS` = `0xffff` , `L4RE_RM_F_CACHE_NORMAL` = `L4RE_DS_F_NORMAL` ,  
`L4RE_RM_F_CACHE_BUFFERED` = `L4RE_DS_F_BUFFERABLE` , `L4RE_RM_F_CACHE_UNCACHED`  
= `L4RE_DS_F_UNCACHABLE` ,  
`L4RE_RM_F_SEARCH_ADDR` = `0x020000` , `L4RE_RM_F_IN_AREA` = `0x040000` , `L4RE_RM_F_EAGER_MAP`  
= `0x080000` , `L4RE_RM_F_NO_EAGER_MAP` = `0x100000` ,  
`L4RE_RM_F_ATTACH_FLAGS` = `0x1f0000` }

*Flags for region operations.*

## Functions

- int `l4re_rm_reserve_area` (`l4_addr_t` \*start, unsigned long size, `l4re_rm_flags_t` flags, unsigned char align) `L4_NOTHROW`  
*Reserve the given area in the region map.*
- int `l4re_rm_free_area` (`l4_addr_t` addr) `L4_NOTHROW`  
*Free an area from the region map.*
- int `l4re_rm_attach` (void \*\*start, unsigned long size, `l4re_rm_flags_t` flags, `l4re_ds_t` mem, `l4re_rm_offset_t` offs, unsigned char align) `L4_NOTHROW`  
*Attach a data space to a region.*
- int `l4re_rm_detach` (void \*addr) `L4_NOTHROW`  
*Detach and unmap a region from the address space in the current task.*
- int `l4re_rm_detach_ds` (void \*addr, `l4re_ds_t` \*ds) `L4_NOTHROW`  
*Detach and unmap a region and return affected dataspace in the current task.*
- int `l4re_rm_detach_unmap` (`l4_addr_t` addr, `l4_cap_idx_t` task) `L4_NOTHROW`  
*Detach and unmap in specified task.*
- int `l4re_rm_detach_ds_unmap` (void \*addr, `l4re_ds_t` \*ds, `l4_cap_idx_t` task) `L4_NOTHROW`  
*Detach and unmap in specified task.*
- int `l4re_rm_find` (`l4_addr_t` \*addr, unsigned long \*size, `l4re_rm_offset_t` \*offset, `l4re_rm_flags_t` \*flags, `l4re_ds_t` \*m) `L4_NOTHROW`  
*Find a region given an address and size.*
- int `l4re_rm_get_info` (`l4_addr_t` addr, char \*name, unsigned int len, `l4re_rm_offset_t` \*backing\_offset) `L4_NOTHROW`  
*Return auxiliary information of a region.*
- void `l4re_rm_show_lists` (void) `L4_NOTHROW`  
*Dump region map internal data structures.*
- int `l4re_rm_reserve_area_srv` (`l4_cap_idx_t` rm, `l4_addr_t` \*start, unsigned long size, `l4re_rm_flags_t` flags, unsigned char align) `L4_NOTHROW`
- int `l4re_rm_free_area_srv` (`l4_cap_idx_t` rm, `l4_addr_t` addr) `L4_NOTHROW`
- int `l4re_rm_attach_srv` (`l4_cap_idx_t` rm, void \*\*start, unsigned long size, `l4re_rm_flags_t` flags, `l4re_ds_t` mem, `l4re_rm_offset_t` offs, unsigned char align) `L4_NOTHROW`
- int `l4re_rm_detach_srv` (`l4_cap_idx_t` rm, `l4_addr_t` addr, `l4re_ds_t` \*ds, `l4_cap_idx_t` task) `L4_NOTHROW`
- int `l4re_rm_find_srv` (`l4_cap_idx_t` rm, `l4_addr_t` \*addr, unsigned long \*size, `l4re_rm_offset_t` \*offset, `l4re_rm_flags_t` \*flags, `l4re_ds_t` \*m) `L4_NOTHROW`
- int `l4re_rm_get_info_srv` (`l4_cap_idx_t` rm, `l4_addr_t` addr, char \*name, unsigned int len, `l4re_rm_offset_t` \*backing\_offset) `L4_NOTHROW`
- void `l4re_rm_show_lists_srv` (`l4_cap_idx_t` rm) `L4_NOTHROW`  
*Dump region map internal data structures.*

## 16.295.1 Detailed Description

Region map interface, C interface.

Definition in file [rm.h](#).

## 16.296 rm.h

[Go to the documentation of this file.](#)

```

00001
00005 /*
00006  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00007  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00008  *      economic rights: Technische Universität Dresden (Germany)
00009  *
00010  * License: see LICENSE.spdx (in this directory or the directories above)
00011  */
00012 #pragma once
00013
00019
00020 #include <l4/re/env.h>
00021 #include <l4/re/c/dataspace.h>
00022 #include <l4/sys/compiler.h>
00023
00024 L4_BEGIN_DECLS
00025
00030 enum l4re_rm_flags_values {
00031     L4RE_RM_F_R      = L4RE_DS_F_R,
00032     L4RE_RM_F_W      = L4RE_DS_F_W,
00033     L4RE_RM_F_X      = L4RE_DS_F_X,
00034     L4RE_RM_F_RX     = L4RE_DS_F_RX,
00035     L4RE_RM_F_RW     = L4RE_DS_F_RW,
00036     L4RE_RM_F_RWX    = L4RE_DS_F_RWX,
00037
00038     L4RE_RM_F_KERNEL      = 0x100,
00039     L4RE_RM_F_DETACH_FREE = 0x200,
00040     L4RE_RM_F_PAGER      = 0x400,
00041     L4RE_RM_F_RESERVED   = 0x800,
00042
00043     L4RE_RM_CACHING_SHIFT = 4,
00044
00046     L4RE_RM_F_CACHING      = L4RE_DS_F_CACHING_MASK,
00047
00048     L4RE_RM_REGION_FLAGS = 0xffff,
00049
00051     L4RE_RM_F_CACHE_NORMAL      = L4RE_DS_F_NORMAL,
00052
00054     L4RE_RM_F_CACHE_BUFFERED    = L4RE_DS_F_BUFFERABLE,
00055
00057     L4RE_RM_F_CACHE_UNCACHED    = L4RE_DS_F_UNCACHEABLE,
00058
00059     L4RE_RM_F_SEARCH_ADDR      = 0x020000,
00060     L4RE_RM_F_IN_AREA          = 0x040000,
00061     L4RE_RM_F_EAGER_MAP        = 0x080000,
00062     L4RE_RM_F_NO_EAGER_MAP     = 0x100000,
00063     L4RE_RM_F_ATTACH_FLAGS     = 0x1f0000,
00064 };
00065
00066 typedef l4_uint32_t l4re_rm_flags_t;
00067 typedef l4_uint64_t l4re_rm_offset_t;
00068
00077 L4_CV L4_INLINE int
00078 l4re_rm_reserve_area(l4_addr_t *start, unsigned long size,
00079                     l4re_rm_flags_t flags, unsigned char align) L4_NOTHROW;
00080
00089 L4_CV L4_INLINE int
00090 l4re_rm_free_area(l4_addr_t addr) L4_NOTHROW;
00091
00142 L4_CV L4_INLINE int
00143 l4re_rm_attach(void **start, unsigned long size, l4re_rm_flags_t flags,
00144               l4re_ds_t mem, l4re_rm_offset_t offs,
00145               unsigned char align) L4_NOTHROW;
00146
00147
00165 L4_CV L4_INLINE int
00166 l4re_rm_detach(void *addr) L4_NOTHROW;
00167
00187 L4_CV L4_INLINE int

```

```

00188 l4re_rm_detach_ds(void *addr, l4re_ds_t *ds) L4_NOTHROW;
00189
00201 L4_CV L4_INLINE int
00202 l4re_rm_detach_unmap(l4_addr_t addr, l4_cap_idx_t task) L4_NOTHROW;
00203
00218 L4_CV L4_INLINE int
00219 l4re_rm_detach_ds_unmap(void *addr, l4re_ds_t *ds,
00220                          l4_cap_idx_t task) L4_NOTHROW;
00221
00222
00229 L4_CV L4_INLINE int
00230 l4re_rm_find(l4_addr_t *addr, unsigned long *size,
00231             l4re_rm_offset_t *offset,
00232             l4re_rm_flags_t *flags, l4re_ds_t *m) L4_NOTHROW;
00233
00241 L4_CV L4_INLINE int
00242 l4re_rm_get_info(l4_addr_t addr,
00243                 char *name, unsigned int len,
00244                 l4re_rm_offset_t *backing_offset) L4_NOTHROW;
00245
00246
00253 L4_CV L4_INLINE void
00254 l4re_rm_show_lists(void) L4_NOTHROW;
00255
00256
00257 /*
00258  * Variants of functions that also take a capability of the region map
00259  * service.
00260  */
00261
00262
00267 L4_CV int
00268 l4re_rm_reserve_area_srv(l4_cap_idx_t rm, l4_addr_t *start, unsigned long size,
00269                          l4re_rm_flags_t flags, unsigned char align) L4_NOTHROW;
00270
00275 L4_CV int
00276 l4re_rm_free_area_srv(l4_cap_idx_t rm, l4_addr_t addr) L4_NOTHROW;
00277
00282 L4_CV int
00283 l4re_rm_attach_srv(l4_cap_idx_t rm, void **start, unsigned long size,
00284                   l4re_rm_flags_t flags, l4re_ds_t mem,
00285                   l4re_rm_offset_t offs,
00286                   unsigned char align) L4_NOTHROW;
00287
00288
00293 L4_CV int
00294 l4re_rm_detach_srv(l4_cap_idx_t rm, l4_addr_t addr,
00295                   l4re_ds_t *ds, l4_cap_idx_t task) L4_NOTHROW;
00296
00297
00302 L4_CV int
00303 l4re_rm_find_srv(l4_cap_idx_t rm, l4_addr_t *addr,
00304                 unsigned long *size, l4re_rm_offset_t *offset,
00305                 l4re_rm_flags_t *flags, l4re_ds_t *m) L4_NOTHROW;
00306
00307
00312 L4_CV int
00313 l4re_rm_get_info_srv(l4_cap_idx_t rm, l4_addr_t addr,
00314                     char *name, unsigned int len,
00315                     l4re_rm_offset_t *backing_offset) L4_NOTHROW;
00316
00321 L4_CV void
00322 l4re_rm_show_lists_srv(l4_cap_idx_t rm) L4_NOTHROW;
00323
00324
00325 /***** Implementations *****/
00326
00327 L4_CV L4_INLINE int
00328 l4re_rm_reserve_area(l4_addr_t *start, unsigned long size,
00329                      l4re_rm_flags_t flags, unsigned char align) L4_NOTHROW
00330 {
00331     return l4re_rm_reserve_area_srv(l4re_global_env->rm, start, size,
00332                                     flags, align);
00333 }
00334
00335 L4_CV L4_INLINE int
00336 l4re_rm_free_area(l4_addr_t addr) L4_NOTHROW
00337 {
00338     return l4re_rm_free_area_srv(l4re_global_env->rm, addr);
00339 }
00340
00341 L4_CV L4_INLINE int
00342 l4re_rm_attach(void **start, unsigned long size, l4re_rm_flags_t flags,
00343               l4re_ds_t mem, l4re_rm_offset_t offs,
00344               unsigned char align) L4_NOTHROW
00345 {
00346     return l4re_rm_attach_srv(l4re_global_env->rm, start, size,

```

```

00347             flags, mem, offs, align);
00348 }
00349
00350
00351 L4_CV L4_INLINE int
00352 l4re_rm_detach(void *addr) L4_NOTHROW
00353 {
00354     return l4re_rm_detach_srv(l4re_global_env->rm,
00355                               (l4_addr_t)addr, 0, L4_BASE_TASK_CAP);
00356 }
00357
00358 L4_CV L4_INLINE int
00359 l4re_rm_detach_unmap(l4_addr_t addr, l4_cap_idx_t task) L4_NOTHROW
00360 {
00361     return l4re_rm_detach_srv(l4re_global_env->rm, addr, 0, task);
00362 }
00363
00364 L4_CV L4_INLINE int
00365 l4re_rm_detach_ds(void *addr, l4re_ds_t *ds) L4_NOTHROW
00366 {
00367     return l4re_rm_detach_srv(l4re_global_env->rm, (l4_addr_t)addr,
00368                               ds, L4_BASE_TASK_CAP);
00369 }
00370
00371 L4_CV L4_INLINE int
00372 l4re_rm_detach_ds_unmap(void *addr, l4re_ds_t *ds, l4_cap_idx_t task) L4_NOTHROW
00373 {
00374     return l4re_rm_detach_srv(l4re_global_env->rm, (l4_addr_t)addr,
00375                               ds, task);
00376 }
00377
00378 L4_CV L4_INLINE int
00379 l4re_rm_find(l4_addr_t *addr, unsigned long *size,
00380             l4re_rm_offset_t *offset,
00381             l4re_rm_flags_t *flags, l4re_ds_t *m) L4_NOTHROW
00382 {
00383     return l4re_rm_find_srv(l4re_global_env->rm, addr, size, offset, flags, m);
00384 }
00385
00386 L4_CV L4_INLINE void
00387 l4re_rm_show_lists(void) L4_NOTHROW
00388 {
00389     l4re_rm_show_lists_srv(l4re_global_env->rm);
00390 }
00391
00392
00393
00394 L4_CV L4_INLINE int
00395 l4re_rm_get_info(l4_addr_t addr, char *name, unsigned int len,
00396                 l4re_rm_offset_t *backing_offset) L4_NOTHROW
00397 {
00398     return l4re_rm_get_info_srv(l4re_global_env->rm, addr, name, len,
00399                               backing_offset);
00400 }
00401
00402 L4_END_DECLS

```

## 16.297 l4/re/c/util/cap\_alloc.h File Reference


Capability allocator C interface.

```

#include <l4/sys/types.h>
#include <l4/sys/linkage.h>

```

Include dependency graph for `cap_alloc.h`:



## Functions

- `L4_BEGIN_DECLS l4_cap_idx_t l4re_util_cap_alloc (void) L4_NOTHROW`  
Get free capability index at capability allocator.
- `void l4re_util_cap_free (l4_cap_idx_t cap) L4_NOTHROW`  
Return capability index to capability allocator.
- `void l4re_util_cap_free_um (l4_cap_idx_t cap) L4_NOTHROW`  
Return capability index to capability allocator, and unmaps the object.
- `long l4re_util_cap_last (void) L4_NOTHROW`  
Return last capability index the allocator can return.

## 16.297.1 Detailed Description

Capability allocator C interface.

Definition in file [cap\\_alloc.h](#).

## 16.298 cap\_alloc.h

[Go to the documentation of this file.](#)

```

00001
00005 /*
00006  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00007  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00008  *      economic rights: Technische Universität Dresden (Germany)
00009  *
00010  * License: see LICENSE.spdx (in this directory or the directories above)
00011  */
00012 #pragma once
00013
00019

```



```

00020 #include <l4/sys/types.h>
00021 #include <l4/sys/linkage.h>
00022
00023 L4_BEGIN_DECLS
00024
00029 L4_CV l4_cap_idx_t
00030 l4re_util_cap_alloc(void) L4_NOTHROW;
00031
00036 L4_CV void
00037 l4re_util_cap_free(l4_cap_idx_t cap) L4_NOTHROW;
00038
00044 L4_CV void
00045 l4re_util_cap_free_um(l4_cap_idx_t cap) L4_NOTHROW;
00046
00052 L4_CV long
00053 l4re_util_cap_last(void) L4_NOTHROW;
00054
00055 L4_END_DECLS

```

## 16.299 l4/re/c/util/kumem\_alloc.h File Reference


Kumem allocator utility C interface.

```
#include <l4/sys/compiler.h>
```

```
#include <l4/sys/types.h>
```

```
#include <l4/sys/linkage.h>
```

Include dependency graph for kumem\_alloc.h:



### Functions

- `L4_BEGIN_DECLS` `int l4re_util_kumem_alloc (l4_addr_t *mem, unsigned pages_order, l4_cap_idx_t task, l4_cap_idx_t rm) L4_NOTHROW`

*Allocate state area.*

### 16.299.1 Detailed Description

Kumem allocator utility C interface.

Definition in file [kumem\\_alloc.h](#).

## 16.299.2 Function Documentation

### 16.299.2.1 l4re\_util\_kumem\_alloc()

```
L4_BEGIN_DECLS int l4re_util_kumem_alloc (
    l4_addr_t * mem,
    unsigned pages_order,
    l4_cap_idx_t task,
    l4_cap_idx_t rm)
```

Allocate state area.

#### Parameters

out	<i>mem</i>	Pointer to memory that has been allocated.
	<i>pages_order</i>	Size to allocate, in log2 pages.
	<i>task</i>	Task to use for allocation.
	<i>rm</i>	Region manager to use for allocation.

#### Return values

0	for success
<0	error code on failure

#### Note

The amount of kernel-user memory that can be allocated at once is limited by the used kernel implementation. The minimum allocatable amount is one page. A portable implementation should not depend on allocations greater than 16KiB to succeed.

#### Examples

[examples/sys/aliens/main.c](#), and [examples/sys/utcb-ipc/main.c](#).

References [L4\\_END\\_DECLS](#), and [L4\\_NOTHROW](#).

## 16.300 kumem\_alloc.h


[Go to the documentation of this file.](#)

```
00001
00005 /*
00006  * (c) 2010 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00007  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00008  *      economic rights: Technische Universität Dresden (Germany)
00009  *
00010  * License: see LICENSE.spdx (in this directory or the directories above)
00011  */
00012 #pragma once
00013
00019
00020 #include <l4/sys/compiler.h>
00021 #include <l4/sys/types.h>
00022 #include <l4/sys/linkage.h>
00023
00024 L4_BEGIN_DECLS
00025
00029 L4_CV int
00030 l4re_util_kumem_alloc(l4_addr_t *mem, unsigned pages_order,
00031                      l4_cap_idx_t task, l4_cap_idx_t rm) L4_NOTHROW;
00032
00033 L4_END_DECLS
```

## 16.301 l4/re/c/util/video/goos\_fb.h File Reference

Framebuffer utility functionality.

```
#include <l4/sys/compiler.h>
#include <l4/re/c/video/goos.h>
#include <l4/sys/err.h>
#include <l4/re/c/dataspace.h>
Include dependency graph for goos_fb.h:
```



### 16.301.1 Detailed Description

Framebuffer utility functionality.

Definition in file [goos\\_fb.h](#).

## 16.302 goos\_fb.h

[Go to the documentation of this file.](#)

```
00001
00002 /*
00003  * (c) 2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>
00004  * economic rights: Technische Universität Dresden (Germany)
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00008 #pragma once
00009
00010 #include <l4/sys/compiler.h>
00011 #include <l4/re/c/video/goos.h>
00012 #include <l4/sys/err.h>
00013 #include <l4/re/c/dataspace.h>
00014
00015 L4_BEGIN_DECLS
00016
00017 typedef struct
00018 {
00019     unsigned long _obj_buf[6];
00020 } l4re_util_video_goos_fb_t;
```

```


00024
00025 L4_CV int
00026 l4re_util_video_goos_fb_setup_name(l4re_util_video_goos_fb_t *goosfb,
00027                                     char const *name) L4_NOTHROW;
00028
00029 L4_CV void
00030 l4re_util_video_goos_fb_destroy(l4re_util_video_goos_fb_t *goosfb) L4_NOTHROW;
00031
00032 L4_CV int
00033 l4re_util_video_goos_fb_view_info(l4re_util_video_goos_fb_t *goosfb,
00034                                   l4re_video_view_info_t *info) L4_NOTHROW;
00035
00036 L4_CV void *
00037 l4re_util_video_goos_fb_attach_buffer(l4re_util_video_goos_fb_t *goosfb) L4_NOTHROW;
00038
00039 L4_CV int
00040 l4re_util_video_goos_fb_refresh(l4re_util_video_goos_fb_t *goosfb,
00041                                int x, int y, int w, int h) L4_NOTHROW;
00042
00043 L4_CV l4re_ds_t
00044 l4re_util_video_goos_fb_buffer(l4re_util_video_goos_fb_t *goosfb) L4_NOTHROW;
00045
00046 L4_CV l4_cap_idx_t
00047 l4re_util_video_goos_fb_goos(l4re_util_video_goos_fb_t *goosfb) L4_NOTHROW;
00048
00049 L4_END_DECLS

```


## 16.303 l4re/c/video/colors.h File Reference

#include <l4/sys/compiler.h>

Include dependency graph for colors.h:



This graph shows which files directly or indirectly include this file:



## Data Structures

- struct `l4re_video_color_component_t`  
*Color component structure.*
- struct `l4re_video_pixel_info_t`  
*Pixel\_info structure.*

## Typedefs

- typedef struct `l4re_video_color_component_t` **`l4re_video_color_component_t`**  
*Color component structure.*
- typedef struct `l4re_video_pixel_info_t` **`l4re_video_pixel_info_t`**  
*Pixel\_info structure.*

### 16.303.1 Detailed Description

#### Note

The C interface of `L4Re::Video` does *NOT* reflect the full C++ interface on purpose. Use the C++ interface where possible.

Definition in file `colors.h`.

## 16.304 colors.h

[Go to the documentation of this file.](#)

```

00001
00006 /*
00007  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>
00008  *      economic rights: Technische Universität Dresden (Germany)
00009  *
00010  * License: see LICENSE.spdx (in this directory or the directories above)
00011  */
00012 #pragma once
00013
00014 #include <l4/sys/compiler.h>
00015
00020 typedef struct l4re_video_color_component_t
00021 {
00022     unsigned char size;
00023     unsigned char shift;
00024 } __attribute__((packed)) l4re_video_color_component_t;
00025
00030 typedef struct l4re_video_pixel_info_t
00031 {
00032     l4re_video_color_component_t r, g, b, a;
00033     unsigned char bytes_per_pixel;
00034 } l4re_video_pixel_info_t;
00035
00036 L4_BEGIN_DECLS
00037
00038 L4_INLINE L4_CV int
00039 l4re_video_bits_per_pixel(l4re_video_pixel_info_t *p) L4_NOTHROW;
00040
00041 /* ***** */
00042 /* Implementations */
00043
00044 L4_INLINE L4_CV int
00045 l4re_video_bits_per_pixel(l4re_video_pixel_info_t *p) L4_NOTHROW
00046 {
00047     return p->r.size + p->b.size + p->g.size + p->a.size;
00048 }
00049
00050 L4_END_DECLS

```


## 16.305 l4/re/c/video/goos.h File Reference

```


#include <l4/sys/compiler.h>
#include <l4/sys/types.h>
#include <l4/re/c/dataspace.h>
#include <l4/re/c/video/colors.h>
#include <l4/re/c/video/view.h>

```

Include dependency graph for goos.h:



This graph shows which files directly or indirectly include this file:



## Data Structures

- struct [l4re\\_video\\_goos\\_info\\_t](#)  
*Goos information structure.*

## Typedefs

- typedef [l4\\_cap\\_idx\\_t](#) [l4re\\_video\\_goos\\_t](#)  
*Goos object type.*

## Enumerations

- enum [l4re\\_video\\_goos\\_info\\_flags\\_t](#) { [F\\_l4re\\_video\\_goos\\_auto\\_refresh](#) = 0x01 , [F\\_l4re\\_video\\_goos\\_pointer](#) = 0x02 , [F\\_l4re\\_video\\_goos\\_dynamic\\_views](#) = 0x04 , [F\\_l4re\\_video\\_goos\\_dynamic\\_buffers](#) = 0x08 }
- Flags of information on the goos.*

## Functions

- [L4\\_BEGIN\\_DECLS](#) int [l4re\\_video\\_goos\\_info](#) ([l4re\\_video\\_goos\\_t](#) goos, [l4re\\_video\\_goos\\_info\\_t](#) \*ginfo) [L4\\_NOTHROW](#)  
*Get information on a goos.*
- int [l4re\\_video\\_goos\\_refresh](#) ([l4re\\_video\\_goos\\_t](#) goos, int x, int y, int w, int h) [L4\\_NOTHROW](#)  
*Flush a rectangle of pixels of the goos screen.*
- int [l4re\\_video\\_goos\\_create\\_buffer](#) ([l4re\\_video\\_goos\\_t](#) goos, unsigned long size, [l4\\_cap\\_idx\\_t](#) buffer) [L4\\_NOTHROW](#)  
*Create a new buffer (memory buffer) for pixel data.*
- int [l4re\\_video\\_goos\\_delete\\_buffer](#) ([l4re\\_video\\_goos\\_t](#) goos, unsigned idx) [L4\\_NOTHROW](#)  
*Delete a pixel buffer.*
- int [l4re\\_video\\_goos\\_get\\_static\\_buffer](#) ([l4re\\_video\\_goos\\_t](#) goos, unsigned idx, [l4\\_cap\\_idx\\_t](#) buffer) [L4\\_NOTHROW](#)  
*Get the data-space capability of the static pixel buffer.*
- int [l4re\\_video\\_goos\\_create\\_view](#) ([l4re\\_video\\_goos\\_t](#) goos, [l4re\\_video\\_view\\_t](#) \*view) [L4\\_NOTHROW](#)  
*Create a new view (.*
- int [l4re\\_video\\_goos\\_delete\\_view](#) ([l4re\\_video\\_goos\\_t](#) goos, [l4re\\_video\\_view\\_t](#) \*view) [L4\\_NOTHROW](#)  
*Delete a view.*
- int [l4re\\_video\\_goos\\_get\\_view](#) ([l4re\\_video\\_goos\\_t](#) goos, unsigned idx, [l4re\\_video\\_view\\_t](#) \*view) [L4\\_NOTHROW](#)  
*Get a view for the given index.*

## 16.305.1 Detailed Description

### Note

The C interface of L4Re::Video does *NOT* reflect the full C++ interface on purpose. Use the C++ where possible.

Definition in file [goos.h](#).

## 16.306 goos.h

[Go to the documentation of this file.](#)

```

00001
00006 /*
00007  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>
00008  *     economic rights: Technische Universität Dresden (Germany)
00009  *
00010  * License: see LICENSE.spdx (in this directory or the directories above)
00011  */
00012 #pragma once
00013
00014 #include <l4/sys/compiler.h>
00015 #include <l4/sys/types.h>
00016 #include <l4/re/c/dataspace.h>
00017 #include <l4/re/c/video/colors.h>
00018 #include <l4/re/c/video/view.h>
00019
00024
00029 enum l4re_video_goos_info_flags_t
00030 {
00031     F_l4re_video_goos_auto_refresh    = 0x01,
00032     F_l4re_video_goos_pointer        = 0x02,
00033     F_l4re_video_goos_dynamic_views  = 0x04,
00034     F_l4re_video_goos_dynamic_buffers = 0x08,
00035 };
00036
00041 typedef struct
00042 {
00043     unsigned long width;
00044     unsigned long height;
00045     unsigned flags;
00046     unsigned num_static_views;
00047     unsigned num_static_buffers;
00048     l4re_video_pixel_info_t pixel_info;
00049 } l4re_video_goos_info_t;
00050
00055 typedef l4_cap_idx_t l4re_video_goos_t;
00056
00057 L4_BEGIN_DECLS
00058
00070 L4_CV int
00071 l4re_video_goos_info(l4re_video_goos_t goos,
00072                     l4re_video_goos_info_t *ginfo) L4_NOTHROW;
00073
00083 L4_CV int
00084 l4re_video_goos_refresh(l4re_video_goos_t goos, int x, int y, int w,
00085                        int h) L4_NOTHROW;
00086
00098 L4_CV int
00099 l4re_video_goos_create_buffer(l4re_video_goos_t goos, unsigned long size,
00100                              l4_cap_idx_t buffer) L4_NOTHROW;
00101
00109 L4_CV int
00110 l4re_video_goos_delete_buffer(l4re_video_goos_t goos, unsigned idx) L4_NOTHROW;
00111
00122 L4_CV int
00123 l4re_video_goos_get_static_buffer(l4re_video_goos_t goos, unsigned idx,
00124                                  l4_cap_idx_t buffer) L4_NOTHROW;
00125
00132 L4_CV int
00133 l4re_video_goos_create_view(l4re_video_goos_t goos,
00134                             l4re_video_view_t *view) L4_NOTHROW;
00135
00143 L4_CV int
00144 l4re_video_goos_delete_view(l4re_video_goos_t goos,
00145                             l4re_video_view_t *view) L4_NOTHROW;

```



```

00146
00147
00159 L4_CV int
00160 l4re_video_goos_get_view(l4re_video_goos_t goos, unsigned idx,
00161                          l4re_video_view_t *view) L4_NOTHROW;
00162
00163 L4_END_DECLS

```


## 16.307 l4/re/c/video/view.h File Reference

```


#include <l4/sys/compiler.h>
#include <l4/sys/types.h>
#include <l4/re/c/dataspace.h>
#include <l4/re/c/video/colors.h>

```

Include dependency graph for view.h:



This graph shows which files directly or indirectly include this file:



## Data Structures

- struct [l4re\\_video\\_view\\_info\\_t](#)  
*View information structure.*
- struct [l4re\\_video\\_view\\_t](#)  
*C representation of a goos view.*

## Typedefs

- typedef struct [l4re\\_video\\_view\\_info\\_t](#) **[l4re\\_video\\_view\\_info\\_t](#)**  
*View information structure.*
- typedef struct [l4re\\_video\\_view\\_t](#) **[l4re\\_video\\_view\\_t](#)**  
*C representation of a goos view.*

## Enumerations

- enum [l4re\\_video\\_view\\_info\\_flags\\_t](#) {  
[F\\_l4re\\_video\\_view\\_none](#) = 0x00 , [F\\_l4re\\_video\\_view\\_set\\_buffer](#) = 0x01 , [F\\_l4re\\_video\\_view\\_set\\_buffer\\_offset](#) = 0x02 , [F\\_l4re\\_video\\_view\\_set\\_bytes\\_per\\_line](#) = 0x04 ,  
[F\\_l4re\\_video\\_view\\_set\\_pixel](#) = 0x08 , [F\\_l4re\\_video\\_view\\_set\\_position](#) = 0x10 , [F\\_l4re\\_video\\_view\\_dyn\\_allocated](#) = 0x20 , [F\\_l4re\\_video\\_view\\_set\\_background](#) = 0x40 ,  
[F\\_l4re\\_video\\_view\\_set\\_flags](#) = 0x80 , **[F\\_l4re\\_video\\_view\\_fully\\_dynamic](#)** , [F\\_l4re\\_video\\_view\\_above](#) = 0x01000 , [F\\_l4re\\_video\\_view\\_flags\\_mask](#) = 0xff000 }  
*Flags of information on a view.*

## Functions

- [L4\\_BEGIN\\_DECLS](#) int [l4re\\_video\\_view\\_refresh](#) ([l4re\\_video\\_view\\_t](#) \*view, int x, int y, int w, int h) [L4\\_NOTHROW](#)  
*Flush the given rectangle of pixels of the given view.*
- int [l4re\\_video\\_view\\_get\\_info](#) ([l4re\\_video\\_view\\_t](#) \*view, [l4re\\_video\\_view\\_info\\_t](#) \*info) [L4\\_NOTHROW](#)  
*Retrieve information about the given view.*
- int [l4re\\_video\\_view\\_set\\_info](#) ([l4re\\_video\\_view\\_t](#) \*view, [l4re\\_video\\_view\\_info\\_t](#) \*info) [L4\\_NOTHROW](#)  
*Set properties of the view.*
- int [l4re\\_video\\_view\\_set\\_viewport](#) ([l4re\\_video\\_view\\_t](#) \*view, int x, int y, int w, int h, unsigned long bofs) [L4\\_NOTHROW](#)  
*Set the viewport parameters of a view.*
- int [l4re\\_video\\_view\\_stack](#) ([l4re\\_video\\_view\\_t](#) \*view, [l4re\\_video\\_view\\_t](#) \*pivot, int behind) [L4\\_NOTHROW](#)  
*Change the stacking order in the stack of visible views.*

## 16.307.1 Detailed Description

### Note

The C interface of `L4Re::Video` does *NOT* reflect the full C++ interface on purpose. Use the C++ where possible.

Definition in file [view.h](#).

## 16.308 view.h

[Go to the documentation of this file.](#)


```

00001
00006 /*
00007  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>
00008  *      economic rights: Technische Universität Dresden (Germany)
00009  *
00010  * License: see LICENSE.spdx (in this directory or the directories above)
00011  */
00012 #pragma once
00013
00014 #include <l4/sys/compiler.h>
00015 #include <l4/sys/types.h>
00016 #include <l4/re/c/dataspace.h>
00017 #include <l4/re/c/video/colors.h>
00018
00023 enum l4re_video_view_info_flags_t
00024 {
00025     F_l4re_video_view_none           = 0x00,
00026     F_l4re_video_view_set_buffer     = 0x01,
00027     F_l4re_video_view_set_buffer_offset = 0x02,
00028     F_l4re_video_view_set_bytes_per_line = 0x04,
00029     F_l4re_video_view_set_pixel      = 0x08,
00030     F_l4re_video_view_set_position   = 0x10,
00031     F_l4re_video_view_dyn_allocated  = 0x20,
00032     F_l4re_video_view_set_background = 0x40,
00033     F_l4re_video_view_set_flags      = 0x80,
00034     F_l4re_video_view_fully_dynamic  = F_l4re_video_view_set_buffer
00035                                         | F_l4re_video_view_set_buffer_offset
00036                                         | F_l4re_video_view_set_bytes_per_line
00037                                         | F_l4re_video_view_set_pixel
00038                                         | F_l4re_video_view_set_position
00039                                         | F_l4re_video_view_dyn_allocated,
00040
00041     F_l4re_video_view_above          = 0x01000,
00042     F_l4re_video_view_flags_mask     = 0xff000,
00043 };
00044
00049 typedef struct l4re_video_view_info_t
00050 {
00051     unsigned          flags;
00052     unsigned          view_index;
00053     unsigned long     xpos, ypos, width, height;
00054     unsigned long     buffer_offset;
00055     unsigned long     bytes_per_line;
00056     l4re_video_pixel_info_t pixel_info;
00057     unsigned          buffer_index;
00058 } l4re_video_view_info_t;
00059
00060
00068 typedef struct l4re_video_view_t
00069 {
00070     l4_cap_idx_t goos;
00071     unsigned idx;
00072 } l4re_video_view_t;
00073
00074
00075 L4_BEGIN_DECLS
00076
00087 L4_CV int
00088 l4re_video_view_refresh(l4re_video_view_t *view, int x, int y, int w,
00089                        int h) L4_NOTHROW;
00090
00091
00098 L4_CV int
00099 l4re_video_view_get_info(l4re_video_view_t *view,
00100                          l4re_video_view_info_t *info) L4_NOTHROW;
00101
00113 L4_CV int
00114 l4re_video_view_set_info(l4re_video_view_t *view,
00115                           l4re_video_view_info_t *info) L4_NOTHROW;
00116
00133 L4_CV int
00134 l4re_video_view_set_viewport(l4re_video_view_t *view, int x, int y, int w,
00135                               int h, unsigned long bofs) L4_NOTHROW;
00136
00147 L4_CV int
00148 l4re_video_view_stack(l4re_video_view_t *view, l4re_video_view_t *pivot,
00149                       int behind) L4_NOTHROW;
00150
00151 L4_END_DECLS
00152

```



This graph shows which files directly or indirectly include this file:



## Data Structures

- class [L4Re::Dataspace](#)  
*Interface for memory-like objects.*
- struct [L4Re::Dataspace::F](#)  
*Dataspace flags definitions.*
- struct [L4Re::Dataspace::Stats](#)  
*Information about the dataspace.*

## Namespaces

- namespace [L4Re](#)  
*L4Re C++ Interfaces.*

## 16.310.1 Detailed Description

Dataspace interface.

Definition in file [dataspace](#).

## 16.311 dataspace

[Go to the documentation of this file.](#)

```
00001 // -*- Mode: C++ -*-
00002 // vim:ft=cpp
00007 /*
00008  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00009  *               Alexander Warg <warg@os.inf.tu-dresden.de>,
00010  *               Björn Döbel <doebel@os.inf.tu-dresden.de>,
00011  *               Torsten Frenzel <frenzel@os.inf.tu-dresden.de>
00012  *               economic rights: Technische Universität Dresden (Germany)
00013  *
00014  * License: see LICENSE.spdx (in this directory or the directories above)
00015  */
00016
00017 #pragma once
00018
00019 #include <l4/bid_config.h>
00020 #include <l4/sys/types.h>
00021 #include <l4/sys/l4int.h>
00022 #include <l4/sys/capability>
00023 #include <l4/re/protocols.h>
00024 #include <l4/sys/cxx/ipc_types>
00025 #include <l4/sys/cxx/ipc_iface>
00026 #include <l4/sys/cxx/types>
00027
00028 namespace L4Re
00029 {
```

```

00030
00031 // MISSING:
00032 // * size support in map, mapped size in reply
00033
00050 class L4_EXPORT Dataspace :
00051     public L4::Kobject_t<Dataspace, L4::Kobject, L4RE_PROTO_DATASPACE,
00052         L4::Type_info::Demand_t<1> >
00053 {
00054 public:
00055
00057     struct F
00058     {
00059         enum
00060         {
00061             Caching_shift = 4,
00062         };
00063
00070         enum Flags
00071         {
00073             R = L4_FPAGE_RO,
00075             Ro = L4_FPAGE_RO,
00077             RW = L4_FPAGE_RW,
00079             W = L4_FPAGE_W,
00081             X = L4_FPAGE_X,
00083             RX = L4_FPAGE_RX,
00085             RWX = L4_FPAGE_RWX,
00087             Rights_mask = 0x0f,
00088
00091             Normal = 0x00,
00093             Cacheable = Normal,
00095             Bufferable = 0x10,
00097             Uncacheable = 0x20,
00099             Caching_mask = 0x30,
00100         };
00101
00102         friend void enum_bitops_enable(Flags);
00103     };
00104
00105     struct Flags : L4::Types::Flags_ops_t<Flags>
00106     {
00107         unsigned long raw;
00108
00109         Flags() = default;
00110         explicit constexpr Flags(unsigned long f) : raw(f) {}
00111         constexpr Flags(F::Flags f) : raw(f) {}
00112
00113         constexpr bool r() const { return raw & L4_FPAGE_RO; }
00114         constexpr bool w() const { return raw & L4_FPAGE_W; }
00115         constexpr bool x() const { return raw & L4_FPAGE_X; }
00116
00117         constexpr unsigned long fpage_rights() const
00118         { return raw & 0xf; }
00119     };
00120
00121     typedef l4_uint64_t Size;
00122     typedef l4_uint64_t Offset;
00123     typedef l4_uint64_t Map_addr;
00124
00128     struct Stats
00129     {
00130         Size size;
00131         Flags flags;
00132     };
00133
00158     l4_ret_t map(Offset offset, Flags flags, Map_addr local_addr,
00159         Map_addr min_addr, Map_addr max_addr,
00160         L4::Cap<L4::Task> dst = L4::Cap<L4::Task>::Invalid) const noexcept;
00161
00189     l4_ret_t map_region(Offset offset, Flags flags,
00190         Map_addr min_addr, Map_addr max_addr,
00191         L4::Cap<L4::Task> dst = L4::Cap<L4::Task>::Invalid) const noexcept;
00192
00210     L4_RPC(l4_ret_t, clear, (Offset offset, Size size));
00211
00231     L4_RPC(l4_ret_t, allocate, (Offset offset, Size size));
00232
00251     L4_RPC(l4_ret_t, copy_in, (Offset dst_offs, L4::Ipc::Cap<Dataspace> src,
00252         Offset src_offs, Size size));
00253
00259     Size size() const noexcept;
00260
00269     Flags flags() const noexcept;
00270
00279     L4_RPC(l4_ret_t, info, (Stats *stats));
00280
00281     L4_RPC_NF(l4_ret_t, map, (Offset offset, Map_addr spot,
00282         Flags flags, L4::Ipc::Rcv_fpage r,

```

```


00283                                     L4::Ipc::Snd_fpage &fp));
00284
00304 #ifndef CONFIG_MMU
00305     L4_RPC_NF(long, map_info, (l4_addr_t *start_addr, l4_addr_t *end_addr));
00306     inline long map_info([[maybe_unused]] l4_addr_t *start_addr,
00307                          [[maybe_unused]] l4_addr_t *end_addr)
00308     { return 0; }
00309 #else
00310     L4_RPC(long, map_info, (l4_addr_t *start_addr, l4_addr_t *end_addr));
00311 #endif
00312
00313 private:
00314
00315     l4_ret_t __map(Offset offset, unsigned char *order, Flags flags,
00316                  Map_addr local_addr, L4::Cap<L4::Task> dst) const noexcept;
00317
00318 public:
00319     typedef L4::Typeid::Rpcs<map_t, clear_t, info_t, copy_in_t,
00320                          allocate_t, map_info_t> Rpcs;
00321 };
00322
00323 }

```

## 16.312 I4/re/dataspace-sys.h File Reference

Dataspace protocol definition.

This graph shows which files directly or indirectly include this file:



### Namespaces

- namespace [L4Re](#)  
[L4Re](#) C++ Interfaces.

### Enumerations

- enum [L4Re::Dataspace\\_::Opcodes](#)  
*Data-space communication-protocol opcodes.*

### 16.312.1 Detailed Description

Dataspace protocol definition.

Definition in file [dataspace-sys.h](#).

## 16.313 dataspace-sys.h

[Go to the documentation of this file.](#)

```

00001
00005 /*
00006  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00007  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00008  *      economic rights: Technische Universität Dresden (Germany)
00009  *
00010  * License: see LICENSE.spdx (in this directory or the directories above)
00011  */
00012 #pragma once
00013
00014 namespace L4Re
00015 {
00016     namespace Dataspace_
00017     {
00023         enum Opcodes { Map, Clear, Stats, Copy, Take, Release, Allocate };
00024     };
00025 };
00026

```

## 16.314 dbg\_events

```

00001 // vim:ft=cpp
00002
00003 #pragma once
00004
00005 #include <l4/sys/cxx/ipc_epiface>
00006 #include <l4/sys/utcb.h>
00007 #include <l4/re/remote_access>
00008 #include <l4/re/rm>
00009
00010 namespace L4Re {
00011     struct Dbg_events : L4::Kobject_t<Dbg_events, L4::Kobject, 0,
00012                                     L4::Type_info::Demand_t<2> >
00013     {
00014         L4_INLINE_RPC(int, request_backtrace, (l4_exc_regs_t regs,
00015                                             L4::Ipc::Cap<L4Re::Remote_access> raif,
00016                                             L4::Ipc::Cap<L4Re::Rm> rmif));
00017
00018         typedef L4::Typeid::Rpc<request_backtrace_t> Rpc;
00019     };
00020 } // L4Re

```

## 16.315 l4/re/dma\_space File Reference


```

#include <l4/sys/types.h>
#include <l4/sys/l4int.h>
#include <l4/sys/capability>
#include <l4/re/dataspace>
#include <l4/re/protocols.h>
#include <l4/sys/cxx/types>
#include <l4/sys/cxx/ipc_types>
#include <l4/sys/cxx/ipc_iface>


```



Include dependency graph for dma\_space:



This graph shows which files directly or indirectly include this file:



## Data Structures

- class `L4Re::Dma_space`  
*Managed DMA Address Space.*

## Namespaces

- namespace **L4Re**  
*L4Re C++ Interfaces.*

## 16.316 dma\_space

[Go to the documentation of this file.](#)


```

00001 // -*- Mode: C++ -*-
00002 // vim:ft=cpp
00006 /*
00007  * (c) 2014 Alexander Warg <alexander.warg@kernkonzept.com>
00008  *
00009  * License: see LICENSE.spdx (in this directory or the directories above)
00010  */
00011
00012 #pragma once
00013
00014 #include <l4/sys/types.h>
00015 #include <l4/sys/l4int.h>
00016 #include <l4/sys/capability>
00017 #include <l4/re/dataspace>
00018 #include <l4/re/protocols.h>
00019 #include <l4/sys/cxx/types>
00020 #include <l4/sys/cxx/ipc_types>
00021 #include <l4/sys/cxx/ipc_iface>
00022
00023 namespace L4Re
00024 {
00025
00052 class Dma_space :
00053     public L4::Kobject_0t< Dma_space,
00054                          L4RE_PROTO_DMA_SPACE,
00055                          L4::Type_info::Demand_t<1> >
00056 {
00057 public:
00059     typedef l4_uint64_t Dma_addr;
00060
00064     enum Direction
00065     {
00066         Bidirectional,
00067         To_device,
00068         From_device,
00069         None
00070     };
00071
00076     enum Attribute
00077     {
00089         No_sync
00090     };
00091
00097     typedef L4::Types::Flags<Attribute> Attributes;
00098
00104     enum Space_attrib
00105     {
00112         Coherent,
00113
00118         Phys_space
00119     };
00120
00122     typedef L4::Types::Flags<Space_attrib> Space_attribs;
00123
00159     L4_INLINE_RPC(
00160         l4_ret_t, map, (L4::Ipc::Cap<L4Re::Dataspace> src,
00161                        L4Re::Dataspace::Offset offset,
00162                        L4::Ipc::In_out<l4_size_t *> size,
00163                        Attributes attrs, Direction dir,
00164                        Dma_addr *dma_addr));
00165
00176     L4_INLINE_RPC(
00177         l4_ret_t, unmap, (Dma_addr dma_addr,
00178                          l4_size_t size, Attributes attrs, Direction dir));
00179
00202     L4_INLINE_RPC(
00203         l4_ret_t, associate, (L4::Ipc::Opt<L4::Ipc::Cap<L4::Task> > dma_task,
00204                              Space_attribs attr),
00205         L4::Ipc::Call_t<L4_CAP_FPAGE_RW>);
00206
00218     L4_INLINE_RPC(
00219         l4_ret_t, disassociate, (),
00220         L4::Ipc::Call_t<L4_CAP_FPAGE_RW>);
00221
00222     typedef L4::Typeid::Rpcs<map_t, unmap_t, associate_t, disassociate_t> Rpcs;
00223 };
00224
00225 }
```

## 16.317 l4/re/elf\_aux.h File Reference

Auxiliary information for binaries.

```
#include <l4/sys/types.h>
Include dependency graph for elf_aux.h:
```



### Data Structures

- struct `l4re_elf_aux_t`  
*Generic header for each auxiliary vector element.*
- struct `l4re_elf_aux_vma_t`  
*Auxiliary vector element for a reserved virtual memory area.*
- struct `l4re_elf_aux_mword_t`  
*Auxiliary vector element for a single unsigned data word.*

### Macros

- `#define L4RE_ELF_AUX_ELEM const __attribute__((used, section(".ro.l4re_elf_aux"), aligned(sizeof(l4_umword_t))))`  
*Define an auxiliary vector element.*
- `#define L4RE_ELF_AUX_ELEM_T(type, id, tag, val...)`  
*Define an auxiliary vector element.*

### Typedefs

- `typedef struct l4re_elf_aux_t l4re_elf_aux_t`  
*Generic header for each auxiliary vector element.*
- `typedef struct l4re_elf_aux_vma_t l4re_elf_aux_vma_t`  
*Auxiliary vector element for a reserved virtual memory area.*
- `typedef struct l4re_elf_aux_mword_t l4re_elf_aux_mword_t`  
*Auxiliary vector element for a single unsigned data word.*

## Enumerations

- enum {  
L4RE\_ELF\_AUX\_T\_NONE = 0 , L4RE\_ELF\_AUX\_T\_VMA , L4RE\_ELF\_AUX\_T\_STACK\_SIZE ,  
L4RE\_ELF\_AUX\_T\_STACK\_ADDR ,  
L4RE\_ELF\_AUX\_T\_KIP\_ADDR , L4RE\_ELF\_AUX\_T\_EX\_REGS\_FLAGS }

### 16.317.1 Detailed Description

Auxiliary information for binaries.

Definition in file [elf\\_aux.h](#).

## 16.318 elf\_aux.h

[Go to the documentation of this file.](#)

```

00001
00005 /*
00006  * (c) 2009 Alexander Warg <warg@os.inf.tu-dresden.de>
00007  *      economic rights: Technische Universität Dresden (Germany)
00008  *
00009  * License: see LICENSE.spdx (in this directory or the directories above)
00010  */
00011 #pragma once
00012
00013 #include <l4/sys/types.h>
00014
00015
00028
00041 #define L4RE_ELF_AUX_ELEM const __attribute__((used, section(".rol4re_elf_aux"),
    aligned(sizeof(l4_umword_t))))
00042
00056 #define L4RE_ELF_AUX_ELEM_T(type, id, tag, val...) \
00057     static L4RE_ELF_AUX_ELEM type id = {tag, sizeof(type), val}
00058
00059 enum
00060 {
00064     L4RE_ELF_AUX_T_NONE = 0,
00065
00069     L4RE_ELF_AUX_T_VMA,
00070
00075     L4RE_ELF_AUX_T_STACK_SIZE,
00076
00081     L4RE_ELF_AUX_T_STACK_ADDR,
00082
00087     L4RE_ELF_AUX_T_KIP_ADDR,
00088
00092     L4RE_ELF_AUX_T_EX_REGS_FLAGS,
00093 };
00094
00098 typedef struct l4re_elf_aux_t
00099 {
00100     l4_umword_t type;
00101     l4_umword_t length;
00102 } l4re_elf_aux_t;
00103
00107 typedef struct l4re_elf_aux_vma_t
00108 {
00109     l4_umword_t type;
00110     l4_umword_t length;
00111     l4_umword_t start;
00112     l4_umword_t end;
00113 } l4re_elf_aux_vma_t;
00114
00118 typedef struct l4re_elf_aux_mword_t
00119 {
00120     l4_umword_t type;
00121     l4_umword_t length;
00122     l4_umword_t value;
00123 } l4re_elf_aux_mword_t;
00124


```

## 16.319 l4/re/env File Reference


Environment interface.

```
#include <l4/sys/types.h>
#include <l4/re/rm>
#include <l4/re/parent>
#include <l4/re/mem_alloc>
#include <l4/re/log>
#include <l4/re/consts>
#include <l4/re/env.h>
```

Include dependency graph for env:



This graph shows which files directly or indirectly include this file:



### Data Structures

- class [L4Re::Env](#)

*C++ interface of the initial environment that is provided to an [L4](#) task.*

### Namespaces

- namespace [L4](#)  
*[L4](#) low-level kernel interface.*
- namespace [L4Re](#)  
*[L4Re](#) C++ Interfaces.*

## 16.319.1 Detailed Description

Environment interface.

Definition in file [env](#).

## 16.320 env

[Go to the documentation of this file.](#)

```

00001 // -*- Mode: C++ -*-
00002 // vim:ft=cpp
00003 /*
00008 * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00009 *      Alexander Warg <warg@os.inf.tu-dresden.de>,
00010 *      Björn Döbel <doebel@os.inf.tu-dresden.de>
00011 *      economic rights: Technische Universität Dresden (Germany)
00012 *
00013 * License: see LICENSE.spdx (in this directory or the directories above)
00014 */
00015 #pragma once
00016
00017 #include <l4/sys/types.h>
00018
00019 #include <l4/re/rm>
00020 #include <l4/re/parent>
00021 #include <l4/re/mem_alloc>
00022 #include <l4/re/log>
00023 #include <l4/re/consts>
00024
00025 #include <l4/re/env.h>
00026
00027 namespace L4 {
00028 class Scheduler;
00029 }
00030
00034 namespace L4Re
00035 {
00036     class Itas;
00037     struct Dbg_events;
00038
00078     class L4_EXPORT Env
00079     {
00080     private:
00081         l4re_env_t _env;
00082     public:
00083
00087         typedef l4re_env_cap_entry_t Cap_entry;
00088
00096         static Env const *env() noexcept
00097         { return reinterpret_cast<Env*>(l4re_global_env); }
00098
00103         L4::Cap<Parent> parent() const noexcept
00104         { return L4::Cap<Parent>(_env.parent); }
00109         L4::Cap<Mem_alloc> mem_alloc() const noexcept
00110         { return L4::Cap<Mem_alloc>(_env.mem_alloc); }
00114         L4::Cap<L4::Factory> user_factory() const noexcept
00115         { return L4::Cap<L4::Factory>(_env.mem_alloc); }
00120         L4::Cap<Rm> rm() const noexcept
00121         { return L4::Cap<Rm>(_env.rm); }
00130         L4::Cap<Log> log() const noexcept
00131         { return L4::Cap<Log>(_env.log); }
00136         L4::Cap<L4::Thread> main_thread() const noexcept
00137         { return L4::Cap<L4::Thread>(_env.main_thread); }
00142         L4::Cap<L4::Task> task() const noexcept
00143         { return L4::Cap<L4::Task>(L4RE_THIS_TASK_CAP); }
00148         L4::Cap<L4::Factory> factory() const noexcept
00149         { return L4::Cap<L4::Factory>(_env.factory); }
00156         l4_cap_idx_t first_free_cap() const noexcept
00157         { return _env.first_free_cap; }
00162         l4_fpage_t utcb_area() const noexcept
00163         { return _env.utcb_area; }
00171         l4_addr_t first_free_utcb() const noexcept
00172         { return _env.first_free_utcb; }
00173
00178         Cap_entry const *initial_caps() const noexcept
00179         { return _env.caps; }
00180
00189         Cap_entry const *get(char const *name, unsigned l) const noexcept

```

```

00190     { return l4re_env_get_cap_l(name, l, &_env); }
00191
00200     template< typename T >
00201     L4::Cap<T> get_cap(char const *name, unsigned l) const noexcept
00202     {
00203         if (Cap_entry const *e = get(name, l))
00204             return L4::Cap<T>(e->cap);
00205
00206         return L4::Cap<T>(-L4_ENOENT);
00207     }
00208
00215     template< typename T >
00216     L4::Cap<T> get_cap(char const *name) const noexcept
00217     { return get_cap<T>(name, __builtin_strlen(name)); }
00218
00223     void parent(L4::Cap<Parent> const &c) noexcept
00224     { _env.parent = c.cap(); }
00229     void mem_alloc(L4::Cap<Mem_alloc> const &c) noexcept
00230     { _env.mem_alloc = c.cap(); }
00235     void rm(L4::Cap<Rm> const &c) noexcept
00236     { _env.rm = c.cap(); }
00241     void log(L4::Cap<Log> const &c) noexcept
00242     { _env.log = c.cap(); }
00247     void main_thread(L4::Cap<L4::Thread> const &c) noexcept
00248     { _env.main_thread = c.cap(); }
00253     void factory(L4::Cap<L4::Factory> const &c) noexcept
00254     { _env.factory = c.cap(); }
00259     void first_free_cap(l4_cap_idx_t c) noexcept
00260     { _env.first_free_cap = c; }
00265     void utcb_area(l4_fpage_t utcbs) noexcept
00266     { _env.utcb_area = utcbs; }
00271     void first_free_utcb(l4_addr_t u) noexcept
00272     { _env.first_free_utcb = u; }
00273
00279     L4::Cap<L4::Scheduler> scheduler() const noexcept
00280     { return L4::Cap<L4::Scheduler>(_env.scheduler); }
00281
00286     void scheduler(L4::Cap<L4::Scheduler> const &c) noexcept
00287     { _env.scheduler = c.cap(); }
00288
00298     L4::Cap<Itas> itas() const noexcept
00299     { return L4::Cap<Itas>(_env.itas); }
00300
00305     void itas(L4::Cap<Itas> const &c) noexcept
00306     { _env.itas = c.cap(); }
00307
00314     L4::Cap<Dbg_events> dbg_events() const noexcept
00315     { return L4::Cap<Dbg_events>(_env.dbg_events); }
00316
00324     void dbg_events(L4::Cap<Dbg_events> const &dbg_events) noexcept
00325     { _env.dbg_events = dbg_events.cap(); }
00326
00331     void initial_caps(Cap_entry *first) noexcept
00332     { _env.caps = first; }
00333 };
00334 };

```

## 16.321 l4/re/env.h File Reference


Environment interface.

```


#include <l4/sys/consts.h>
#include <l4/sys/types.h>
#include <l4/sys/kip.h>
#include <l4/sys/compiler.h>
#include <l4/re/consts.h>

```

Include dependency graph for env.h:



This graph shows which files directly or indirectly include this file:



## Data Structures

- struct [l4re\\_env\\_cap\\_entry\\_t](#)  
*Entry in the [L4Re](#) environment array for the named initial objects.*
- struct [l4re\\_env\\_t](#)  
*Initial environment data structure.*

## Typedefs

- typedef struct [l4re\\_env\\_cap\\_entry\\_t](#) [l4re\\_env\\_cap\\_entry\\_t](#)  
*Entry in the [L4Re](#) environment array for the named initial objects.*
- typedef struct [l4re\\_env\\_t](#) [l4re\\_env\\_t](#)  
*Initial environment data structure.*

## Functions

- [l4re\\_env\\_t](#) \* [l4re\\_env](#) (void) [L4\\_NOTHROW](#)  
*Get [L4Re](#) initial environment.*
- [l4\\_kernel\\_info\\_t](#) const \* [l4re\\_kip](#) (void) [L4\\_NOTHROW](#)  
*Get Kernel Info Page.*
- [l4\\_cap\\_idx\\_t](#) [l4re\\_env\\_get\\_cap](#) (char const \*name) [L4\\_NOTHROW](#)



*Get the capability selector for the object named name.*

- [l4\\_cap\\_idx\\_t l4re\\_env\\_get\\_cap\\_e](#) (char const \*name, [l4re\\_env\\_t](#) const \*e) [L4\\_NOTHROW](#)

*Get the capability selector for the object named name.*

- [l4re\\_env\\_cap\\_entry\\_t](#) const \* [l4re\\_env\\_get\\_cap\\_l](#) (char const \*name, unsigned l, [l4re\\_env\\_t](#) const \*e) [L4\\_NOTHROW](#)

*Get the full [l4re\\_env\\_cap\\_entry\\_t](#) for the object named name.*

## 16.321.1 Detailed Description

Environment interface.

Definition in file [env.h](#).

## 16.321.2 Typedef Documentation

### 16.321.2.1 l4re\_env\_t

```
typedef struct l4re_env_t l4re_env_t
```

Initial environment data structure.

See also

[Initial environment](#)

## 16.322 env.h

[Go to the documentation of this file.](#)

```
00001
00005 /*
00006  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00007  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00008  *      economic rights: Technische Universität Dresden (Germany)
00009  *
00010  * License: see LICENSE.spdx (in this directory or the directories above)
00011  */
00012 #pragma once
00013
00014 #include <l4/sys/consts.h>
00015 #include <l4/sys/types.h>
00016 #include <l4/sys/kip.h>
00017 #include <l4/sys/compiler.h>
00018
00019 #include <l4/re/consts.h>
00020
00034
00039 typedef struct l4re_env_cap_entry_t
00040 {
00044     l4_cap_idx_t cap;
00045
00050     l4_umword_t flags;
00051
00055     char name[16];
00056 #ifdef __cplusplus
00057
00061     l4re_env_cap_entry_t() L4\_NOTHROW : cap(L4\_INVALID\_CAP), flags(~0UL) {}
00062
00070     l4re_env_cap_entry_t(char const *n, l4_cap_idx_t c, l4_umword_t f = 0) L4\_NOTHROW
00071     : cap(c), flags(f)
00072     {
00073         for (unsigned i = 0; i < sizeof(name); ++i, ++n)
00074             {
```

```

00075     name[i] = *n;
00076     if (!*n)
00077         break;
00078     }
00079 }
00080
00081 static bool is_valid_name(char const *n) L4_NOTHROW
00082 {
00083     for (unsigned i = 0; *n; ++i, ++n)
00084         if (i > sizeof(name))
00085             return false;
00086
00087     return true;
00088 }
00089 #endif
00090 } l4re_env_cap_entry_t;
00091
00092
00093 typedef struct l4re_env_t
00094 {
00095     l4_cap_idx_t parent;
00096     l4_cap_idx_t rm;
00097     l4_cap_idx_t mem_alloc;
00098     l4_cap_idx_t log;
00099     l4_cap_idx_t main_thread;
00100     l4_cap_idx_t factory;
00101     l4_cap_idx_t scheduler;
00102     l4_cap_idx_t itas;
00103     l4_cap_idx_t dbg_events;
00104     l4_cap_idx_t first_free_cap;
00105     l4_fpage_t utcb_area;
00106     l4_addr_t first_free_utcb;
00107     l4re_env_cap_entry_t *caps;
00108 } l4re_env_t;
00109
00110 extern l4re_env_t *l4re_global_env;
00111
00112
00113 L4_INLINE l4re_env_t *l4re_env(void) L4_NOTHROW;
00114
00115 /*
00116  * FIXME: this seems to be at the wrong place here
00117  */
00118 L4_INLINE l4_kernel_info_t const *l4re_kip(void) L4_NOTHROW;
00119
00120
00121 L4_INLINE l4_cap_idx_t
00122 l4re_env_get_cap(char const *name) L4_NOTHROW;
00123
00124 L4_INLINE l4_cap_idx_t
00125 l4re_env_get_cap_e(char const *name, l4re_env_t const *e) L4_NOTHROW;
00126
00127 L4_INLINE l4re_env_cap_entry_t const *
00128 l4re_env_get_cap_l(char const *name, unsigned l, l4re_env_t const *e) L4_NOTHROW;
00129
00130 L4_INLINE
00131 l4re_env_t *l4re_env(void) L4_NOTHROW
00132 { return l4re_global_env; }
00133
00134 L4_INLINE
00135 l4_kernel_info_t const *l4re_kip(void) L4_NOTHROW
00136 { return l4_kip(); }
00137
00138 L4_INLINE l4re_env_cap_entry_t const *
00139 l4re_env_get_cap_l(char const *name, unsigned l, l4re_env_t const *e) L4_NOTHROW
00140 {
00141     l4re_env_cap_entry_t const *c = e->caps;
00142     for (; c && c->flags != ~0UL; ++c)
00143     {
00144         unsigned i;
00145         for (i = 0;
00146              i < sizeof(c->name) && i < l && c->name[i] && name[i] && name[i] == c->name[i];
00147              ++i)
00148             ;
00149         if (i == l && (i == sizeof(c->name) || !c->name[i]))
00150             return c;
00151     }
00152     return NULL;
00153 }
00154
00155 L4_INLINE l4_cap_idx_t
00156 l4re_env_get_cap_e(char const *name, l4re_env_t const *e) L4_NOTHROW
00157 {
00158     unsigned l;
00159     l4re_env_cap_entry_t const *r;
00160     for (l = 0; name[l]; ++l) ;

```


```
00212     r = 14re_env_get_cap_1(name, l, e);
00213     if (r)
00214         return r->cap;
00215
00216     return L4_INVALID_CAP;
00217 }
00218
00219 L4_INLINE l4_cap_idx_t
00220 14re_env_get_cap(char const *name) L4_NOTHROW
00221 { return 14re_env_get_cap_e(name, 14re_env()); }
00222 }
```

### 16.323 l4/re/error\_helper File Reference


Error helper.

```
#include <l4/sys/types.h>
#include <l4/cxx/exceptions>
#include <l4/cxx/type_traits>
#include <l4/sys/err.h>
#include <stdarg.h>
#include <stdio.h>
```

Include dependency graph for error\_helper:



This graph shows which files directly or indirectly include this file:



## Namespaces

- namespace [L4Re](#)  
*L4Re C++ Interfaces.*

## Functions

- void [L4Re::throw\\_error](#) (long err, char const \*extra="")  
*Generate C++ exception.*
- [l4\\_ret\\_t](#) [L4Re::chksys](#) ([l4\\_ret\\_t](#) err, char const \*extra="", [l4\\_ret\\_t](#) ret=0)  
*Generate C++ exception on error.*
- [l4\\_ret\\_t](#) [L4Re::chksys](#) ([l4\\_msgtag\\_t](#) const &t, char const \*extra="", [l4\\_utcb\\_t](#) \*utcb=[l4\\_utcb](#)(), [l4\\_ret\\_t](#) ret=0)  
*Generate C++ exception on error.*
- [l4\\_ret\\_t](#) [L4Re::chksys](#) ([l4\\_msgtag\\_t](#) const &t, [l4\\_utcb\\_t](#) \*utcb, char const \*extra="")  
*Generate C++ exception on error.*
- template<typename T>  
T [L4Re::chkcap](#) (T &&cap, char const \*extra="", [l4\\_ret\\_t](#) err=-[L4\\_ENOMEM](#))  
*Check for valid capability or raise C++ exception.*
- [l4\\_msgtag\\_t](#) [L4Re::chkipc](#) ([l4\\_msgtag\\_t](#) tag, char const \*extra="", [l4\\_utcb\\_t](#) \*utcb=[l4\\_utcb](#)())  
*Test a message tag for IPC errors.*

### 16.323.1 Detailed Description

Error helper.

Definition in file [error\\_helper](#).

## 16.324 error\_helper

[Go to the documentation of this file.](#)

```

00001 // vi:set ft=cpp: -- Mode: C++ --
00006 /*
00007  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00008  *             Alexander Warg <warg@os.inf.tu-dresden.de>,
00009  *             Torsten Frenzel <frenzel@os.inf.tu-dresden.de>
00010  *             economic rights: Technische Universität Dresden (Germany)
00011  *
00012  * License: see LICENSE.spdx (in this directory or the directories above)
00013  */
00014 #pragma once
00015
00016 #include <l4/sys/types.h>
00017 #include <l4/cxx/exceptions>
00018 #include <l4/cxx/type_traits>
00019 #include <l4/sys/err.h>
00020
00021 #include <stdarg.h>
00022 #include <stdio.h>
00023
00024 namespace L4Re {
00025
00026 #ifdef __EXCEPTIONS
00027
00037 [[noreturn]] inline void throw_error(long err, char const *extra = "")
00038 {
00039     switch (err)
00040     {
00041     case -L4_ENOENT: throw (L4::Element_not_found(extra));
00042     case -L4_ENOMEM: throw (L4::Out_of_memory(extra));
00043     case -L4_EEXIST: throw (L4::Element_already_exists(extra));
00044     case -L4_ERANGE: throw (L4::Bounds_error(extra));

```

```

00045     default: throw (L4::Runtime_error(err, extra));
00046     }
00047 }
00048
00049 [[noreturn]] inline void throw_error_fmt(l4_ret_t err, char const *const fmt, ...)
00050     __attribute__((format(printf, 2, 3)));
00051 [[noreturn]] inline void throw_error_fmt(l4_ret_t err, char const *const fmt, ...)
00052 {
00053     char extra[80];
00054     va_list argp;
00055     va_start(argp, fmt);
00056     vsnprintf(extra, sizeof(extra), fmt, argp);
00057     va_end(argp);
00058     throw_error(err, extra);
00059 }
00060
00071 inline
00072 l4_ret_t chksys(l4_ret_t err, char const *extra = "", l4_ret_t ret = 0)
00073 {
00074     if (L4_UNLIKELY(err < 0))
00075         throw_error(ret ? ret : err, extra);
00076
00077     return err;
00078 }
00079
00092 inline
00093 l4_ret_t chksys(l4_msgtag_t const &t, char const *extra = "",
00094                 l4_utcb_t *utcb = l4_utcb(), l4_ret_t ret = 0)
00095 {
00096     if (L4_UNLIKELY(t.has_error()))
00097         throw_error(ret ? ret : l4_error_u(t, utcb), extra);
00098     else if (L4_UNLIKELY(t.label() < 0))
00099         throw_error(ret ? ret : t.label(), extra);
00100
00101     return t.label();
00102 }
00103
00115 inline
00116 l4_ret_t chksys(l4_msgtag_t const &t, l4_utcb_t *utcb, char const *extra = "")
00117 { return chksys(t, extra, utcb); }
00118
00119 #if 0
00120 inline
00121 long chksys(l4_ret_t ret, l4_ret_t err, char const *extra = "")
00122 {
00123     if (L4_UNLIKELY(ret < 0))
00124         throw_error(err, extra);
00125
00126     return ret;
00127 }
00128 #endif
00129
00146 template<typename T>
00147 inline
00148 #if __cplusplus >= 201103L
00149 T chkcap(T &&cap, char const *extra = "", l4_ret_t err = -L4_ENOMEM)
00150 #else
00151 T chkcap(T cap, char const *extra = "", l4_ret_t err = -L4_ENOMEM)
00152 #endif
00153 {
00154     if (L4_UNLIKELY(!cap.is_valid()))
00155         throw_error(err ? err : cap.invalid_cap_error(), extra);
00156
00157 #if __cplusplus >= 201103L
00158     return cxx::forward<T>(cap);
00159 #else
00160     return cap;
00161 #endif
00162 }
00163
00178 inline
00179 l4_msgtag_t
00180 chkipc(l4_msgtag_t tag, char const *extra = "",
00181         l4_utcb_t *utcb = l4_utcb())
00182 {
00183     if (L4_UNLIKELY(tag.has_error()))
00184         chksys(l4_error_u(tag, utcb), extra);
00185
00186     return tag;
00187 }
00188 #endif
00189
00190 }

```

## 16.325 event-sys.h

```

00001 /*
00002  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00003  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00004  *      economic rights: Technische Universität Dresden (Germany)
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00008 #pragma once
00009 namespace L4Re
00010 {
00011     namespace Event_
00012     {
00013         enum Opcodes
00014         {
00015             Get, Get_num_streams, Get_stream_info, Get_stream_info_for_id,
00016             Get_axis_info, Get_stream_state_for_id
00017         };
00018     };
00019 };
00020 
```

## 16.326 event\_enums.h

```

00001 #pragma once
00002
00003 /*
00004  *
00005  *
00006  * Constants for L4Re events ...
00007  */
00008
00009
00010 enum L4Re_events_key
00011 {
00012     L4RE_KEY_RESERVED           = 0,
00013     L4RE_KEY_ESC                = 1,
00014     L4RE_KEY_1                  = 2,
00015     L4RE_KEY_2                  = 3,
00016     L4RE_KEY_3                  = 4,
00017     L4RE_KEY_4                  = 5,
00018     L4RE_KEY_5                  = 6,
00019     L4RE_KEY_6                  = 7,
00020     L4RE_KEY_7                  = 8,
00021     L4RE_KEY_8                  = 9,
00022     L4RE_KEY_9                  = 10,
00023     L4RE_KEY_0                  = 11,
00024     L4RE_KEY_MINUS              = 12,
00025     L4RE_KEY_EQUAL              = 13,
00026     L4RE_KEY_BACKSPACE         = 14,
00027     L4RE_KEY_TAB                = 15,
00028     L4RE_KEY_Q                  = 16,
00029     L4RE_KEY_W                  = 17,
00030     L4RE_KEY_E                  = 18,
00031     L4RE_KEY_R                  = 19,
00032     L4RE_KEY_T                  = 20,
00033     L4RE_KEY_Y                  = 21,
00034     L4RE_KEY_U                  = 22,
00035     L4RE_KEY_I                  = 23,
00036     L4RE_KEY_O                  = 24,
00037     L4RE_KEY_P                  = 25,
00038     L4RE_KEY_LEFTBRACE         = 26,
00039     L4RE_KEY_RIGHTBRACE        = 27,
00040     L4RE_KEY_ENTER              = 28,
00041     L4RE_KEY_LEFTCTRL          = 29,
00042     L4RE_KEY_A                  = 30,
00043     L4RE_KEY_S                  = 31,
00044     L4RE_KEY_D                  = 32,
00045     L4RE_KEY_F                  = 33,
00046     L4RE_KEY_G                  = 34,
00047     L4RE_KEY_H                  = 35,
00048     L4RE_KEY_J                  = 36,
00049     L4RE_KEY_K                  = 37,
00050     L4RE_KEY_L                  = 38,
00051     L4RE_KEY_SEMICOLON         = 39,
00052     L4RE_KEY_APOSTROPHE        = 40,
00053     L4RE_KEY_GRAVE             = 41,
00054     L4RE_KEY_LEFTSHIFT         = 42,
00055     L4RE_KEY_BACKSLASH         = 43,
00056     L4RE_KEY_Z                  = 44,
00057     L4RE_KEY_X                  = 45,
00058     L4RE_KEY_C                  = 46,

```

```
00059 L4RE_KEY_V = 47,
00060 L4RE_KEY_B = 48,
00061 L4RE_KEY_N = 49,
00062 L4RE_KEY_M = 50,
00063 L4RE_KEY_COMMA = 51,
00064 L4RE_KEY_DOT = 52,
00065 L4RE_KEY_SLASH = 53,
00066 L4RE_KEY_RIGHTSHIFT = 54,
00067 L4RE_KEY_KPASTERISK = 55,
00068 L4RE_KEY_LEFTALT = 56,
00069 L4RE_KEY_SPACE = 57,
00070 L4RE_KEY_CAPSLOCK = 58,
00071 L4RE_KEY_F1 = 59,
00072 L4RE_KEY_F2 = 60,
00073 L4RE_KEY_F3 = 61,
00074 L4RE_KEY_F4 = 62,
00075 L4RE_KEY_F5 = 63,
00076 L4RE_KEY_F6 = 64,
00077 L4RE_KEY_F7 = 65,
00078 L4RE_KEY_F8 = 66,
00079 L4RE_KEY_F9 = 67,
00080 L4RE_KEY_F10 = 68,
00081 L4RE_KEY_NUMLOCK = 69,
00082 L4RE_KEY_SCROLLLOCK = 70,
00083 L4RE_KEY_KP7 = 71,
00084 L4RE_KEY_KP8 = 72,
00085 L4RE_KEY_KP9 = 73,
00086 L4RE_KEY_KPMINUS = 74,
00087 L4RE_KEY_KP4 = 75,
00088 L4RE_KEY_KP5 = 76,
00089 L4RE_KEY_KP6 = 77,
00090 L4RE_KEY_KPPLUS = 78,
00091 L4RE_KEY_KP1 = 79,
00092 L4RE_KEY_KP2 = 80,
00093 L4RE_KEY_KP3 = 81,
00094 L4RE_KEY_KP0 = 82,
00095 L4RE_KEY_KPDOT = 83,
00096 L4RE_KEY_ZENKAKUHANKAKU = 85,
00097 L4RE_KEY_102ND = 86,
00098 L4RE_KEY_F11 = 87,
00099 L4RE_KEY_F12 = 88,
00100 L4RE_KEY_RO = 89,
00101 L4RE_KEY_KATAKANA = 90,
00102 L4RE_KEY_HIRAGANA = 91,
00103 L4RE_KEY_HENKAN = 92,
00104 L4RE_KEY_KATAKANAHIRAGANA = 93,
00105 L4RE_KEY_MUHENKAN = 94,
00106 L4RE_KEY_KPJPCOMMA = 95,
00107 L4RE_KEY_KPENTER = 96,
00108 L4RE_KEY_RIGHTCTRL = 97,
00109 L4RE_KEY_KPSLASH = 98,
00110 L4RE_KEY_SYSRQ = 99,
00111 L4RE_KEY_RIGHTALT = 100,
00112 L4RE_KEY_LINEFEED = 101,
00113 L4RE_KEY_HOME = 102,
00114 L4RE_KEY_UP = 103,
00115 L4RE_KEY_PAGEUP = 104,
00116 L4RE_KEY_LEFT = 105,
00117 L4RE_KEY_RIGHT = 106,
00118 L4RE_KEY_END = 107,
00119 L4RE_KEY_DOWN = 108,
00120 L4RE_KEY_PAGEDOWN = 109,
00121 L4RE_KEY_INSERT = 110,
00122 L4RE_KEY_DELETE = 111,
00123 L4RE_KEY_MACRO = 112,
00124 L4RE_KEY_MUTE = 113,
00125 L4RE_KEY_VOLUMEDOWN = 114,
00126 L4RE_KEY_VOLUMEUP = 115,
00127 L4RE_KEY_POWER = 116,
00128 L4RE_KEY_KPEQUAL = 117,
00129 L4RE_KEY_KPPLUSMINUS = 118,
00130 L4RE_KEY_PAUSE = 119,
00131 L4RE_KEY_KPCOMMA = 121,
00132 L4RE_KEY_HANGEUL = 122,
00133 L4RE_KEY_HANGUEL = L4RE_KEY_HANGEUL,
00134 L4RE_KEY_HANJA = 123,
00135 L4RE_KEY_YEN = 124,
00136 L4RE_KEY_LEFTMETA = 125,
00137 L4RE_KEY_RIGHTMETA = 126,
00138 L4RE_KEY_COMPOSE = 127,
00139 L4RE_KEY_STOP = 128,
00140 L4RE_KEY_AGAIN = 129,
00141 L4RE_KEY_PROPS = 130,
00142 L4RE_KEY_UNDO = 131,
00143 L4RE_KEY_FRONT = 132,
00144 L4RE_KEY_COPY = 133,
00145 L4RE_KEY_OPEN = 134,
```

00146	L4RE_KEY_PASTE	= 135,
00147	L4RE_KEY_FIND	= 136,
00148	L4RE_KEY_CUT	= 137,
00149	L4RE_KEY_HELP	= 138,
00150	L4RE_KEY_MENU	= 139,
00151	L4RE_KEY_CALC	= 140,
00152	L4RE_KEY_SETUP	= 141,
00153	L4RE_KEY_SLEEP	= 142,
00154	L4RE_KEY_WAKEUP	= 143,
00155	L4RE_KEY_FILE	= 144,
00156	L4RE_KEY_SENDFILE	= 145,
00157	L4RE_KEY_DELETEFILE	= 146,
00158	L4RE_KEY_XFER	= 147,
00159	L4RE_KEY_PROG1	= 148,
00160	L4RE_KEY_PROG2	= 149,
00161	L4RE_KEY_WWW	= 150,
00162	L4RE_KEY_MSDOS	= 151,
00163	L4RE_KEY_COFFEE	= 152,
00164	L4RE_KEY_DIRECTION	= 153,
00165	L4RE_KEY_CYCLEWINDOWS	= 154,
00166	L4RE_KEY_MAIL	= 155,
00167	L4RE_KEY_BOOKMARKS	= 156,
00168	L4RE_KEY_COMPUTER	= 157,
00169	L4RE_KEY_BACK	= 158,
00170	L4RE_KEY_FORWARD	= 159,
00171	L4RE_KEY_CLOSECD	= 160,
00172	L4RE_KEY_EJECTCD	= 161,
00173	L4RE_KEY_EJECTCLOSECD	= 162,
00174	L4RE_KEY_NEXTSONG	= 163,
00175	L4RE_KEY_PLAYPAUSE	= 164,
00176	L4RE_KEY_PREVIOUSSONG	= 165,
00177	L4RE_KEY_STOPCD	= 166,
00178	L4RE_KEY_RECORD	= 167,
00179	L4RE_KEY_REWIND	= 168,
00180	L4RE_KEY_PHONE	= 169,
00181	L4RE_KEY_ISO	= 170,
00182	L4RE_KEY_CONFIG	= 171,
00183	L4RE_KEY_HOMEPAGE	= 172,
00184	L4RE_KEY_REFRESH	= 173,
00185	L4RE_KEY_EXIT	= 174,
00186	L4RE_KEY_MOVE	= 175,
00187	L4RE_KEY_EDIT	= 176,
00188	L4RE_KEY_SCROLLUP	= 177,
00189	L4RE_KEY_SCROLLDOWN	= 178,
00190	L4RE_KEY_KPLEFTPAREN	= 179,
00191	L4RE_KEY_KPRIGHTPAREN	= 180,
00192	L4RE_KEY_NEW	= 181,
00193	L4RE_KEY_REDO	= 182,
00194	L4RE_KEY_F13	= 183,
00195	L4RE_KEY_F14	= 184,
00196	L4RE_KEY_F15	= 185,
00197	L4RE_KEY_F16	= 186,
00198	L4RE_KEY_F17	= 187,
00199	L4RE_KEY_F18	= 188,
00200	L4RE_KEY_F19	= 189,
00201	L4RE_KEY_F20	= 190,
00202	L4RE_KEY_F21	= 191,
00203	L4RE_KEY_F22	= 192,
00204	L4RE_KEY_F23	= 193,
00205	L4RE_KEY_F24	= 194,
00206	L4RE_KEY_PLAYCD	= 200,
00207	L4RE_KEY_PAUSECD	= 201,
00208	L4RE_KEY_PROG3	= 202,
00209	L4RE_KEY_PROG4	= 203,
00210	L4RE_KEY_SUSPEND	= 205,
00211	L4RE_KEY_CLOSE	= 206,
00212	L4RE_KEY_PLAY	= 207,
00213	L4RE_KEY_FASTFORWARD	= 208,
00214	L4RE_KEY_BASSBOOST	= 209,
00215	L4RE_KEY_PRINT	= 210,
00216	L4RE_KEY_HP	= 211,
00217	L4RE_KEY_CAMERA	= 212,
00218	L4RE_KEY_SOUND	= 213,
00219	L4RE_KEY_QUESTION	= 214,
00220	L4RE_KEY_EMAIL	= 215,
00221	L4RE_KEY_CHAT	= 216,
00222	L4RE_KEY_SEARCH	= 217,
00223	L4RE_KEY_CONNECT	= 218,
00224	L4RE_KEY_FINANCE	= 219,
00225	L4RE_KEY_SPORT	= 220,
00226	L4RE_KEY_SHOP	= 221,
00227	L4RE_KEY_ALTERASE	= 222,
00228	L4RE_KEY_CANCEL	= 223,
00229	L4RE_KEY_BRIGHTNESSDOWN	= 224,
00230	L4RE_KEY_BRIGHTNESSUP	= 225,
00231	L4RE_KEY_MEDIA	= 226,
00232	L4RE_KEY_SWITCHVIDEOMODE	= 227,



```
00233 L4RE_KEY_KBDILLUMTOGGLE = 228,
00234 L4RE_KEY_KBDILLUMDOWN   = 229,
00235 L4RE_KEY_KBDILLUMUP    = 230,
00236 L4RE_KEY_SEND            = 231,
00237 L4RE_KEY_REPLY           = 232,
00238 L4RE_KEY_FORWARDMAIL    = 233,
00239 L4RE_KEY_SAVE            = 234,
00240 L4RE_KEY_DOCUMENTS       = 235,
00241 L4RE_KEY_UNKNOWN        = 240,
00242 L4RE_KEY_OK              = 0x160,
00243 L4RE_KEY_SELECT          = 0x161,
00244 L4RE_KEY_GOTO           = 0x162,
00245 L4RE_KEY_CLEAR           = 0x163,
00246 L4RE_KEY_POWER2         = 0x164,
00247 L4RE_KEY_OPTION        = 0x165,
00248 L4RE_KEY_INFO           = 0x166,
00249 L4RE_KEY_TIME            = 0x167,
00250 L4RE_KEY_VENDOR         = 0x168,
00251 L4RE_KEY_ARCHIVE        = 0x169,
00252 L4RE_KEY_PROGRAM        = 0x16a,
00253 L4RE_KEY_CHANNEL        = 0x16b,
00254 L4RE_KEY_FAVORITES     = 0x16c,
00255 L4RE_KEY_EPG            = 0x16d,
00256 L4RE_KEY_PVR           = 0x16e,
00257 L4RE_KEY_MHP           = 0x16f,
00258 L4RE_KEY_LANGUAGE       = 0x170,
00259 L4RE_KEY_TITLE          = 0x171,
00260 L4RE_KEY_SUBTITLE        = 0x172,
00261 L4RE_KEY_ANGLE           = 0x173,
00262 L4RE_KEY_ZOOM           = 0x174,
00263 L4RE_KEY_MODE           = 0x175,
00264 L4RE_KEY_KEYBOARD       = 0x176,
00265 L4RE_KEY_SCREEN        = 0x177,
00266 L4RE_KEY_PC             = 0x178,
00267 L4RE_KEY_TV             = 0x179,
00268 L4RE_KEY_TV2            = 0x17a,
00269 L4RE_KEY_VCR            = 0x17b,
00270 L4RE_KEY_VCR2           = 0x17c,
00271 L4RE_KEY_SAT           = 0x17d,
00272 L4RE_KEY_SAT2          = 0x17e,
00273 L4RE_KEY_CD             = 0x17f,
00274 L4RE_KEY_TAPE          = 0x180,
00275 L4RE_KEY_RADIO         = 0x181,
00276 L4RE_KEY_TUNER         = 0x182,
00277 L4RE_KEY_PLAYER        = 0x183,
00278 L4RE_KEY_TEXT          = 0x184,
00279 L4RE_KEY_DVD           = 0x185,
00280 L4RE_KEY_AUX           = 0x186,
00281 L4RE_KEY_MP3           = 0x187,
00282 L4RE_KEY_AUDIO         = 0x188,
00283 L4RE_KEY_VIDEO         = 0x189,
00284 L4RE_KEY_DIRECTORY     = 0x18a,
00285 L4RE_KEY_LIST          = 0x18b,
00286 L4RE_KEY_MEMO          = 0x18c,
00287 L4RE_KEY_CALENDAR      = 0x18d,
00288 L4RE_KEY_RED            = 0x18e,
00289 L4RE_KEY_GREEN         = 0x18f,
00290 L4RE_KEY_YELLOW        = 0x190,
00291 L4RE_KEY_BLUE          = 0x191,
00292 L4RE_KEY_CHANNELUP     = 0x192,
00293 L4RE_KEY_CHANNELDOWN   = 0x193,
00294 L4RE_KEY_FIRST         = 0x194,
00295 L4RE_KEY_LAST          = 0x195,
00296 L4RE_KEY_AB            = 0x196,
00297 L4RE_KEY_NEXT          = 0x197,
00298 L4RE_KEY_RESTART       = 0x198,
00299 L4RE_KEY_SLOW          = 0x199,
00300 L4RE_KEY_SHUFFLE       = 0x19a,
00301 L4RE_KEY_BREAK         = 0x19b,
00302 L4RE_KEY_PREVIOUS     = 0x19c,
00303 L4RE_KEY_DIGITS       = 0x19d,
00304 L4RE_KEY_TEEN         = 0x19e,
00305 L4RE_KEY_TWEN         = 0x19f,
00306 L4RE_KEY_DEL_EOL      = 0x1c0,
00307 L4RE_KEY_DEL_EOS      = 0x1c1,
00308 L4RE_KEY_INS_LINE      = 0x1c2,
00309 L4RE_KEY_DEL_LINE    = 0x1c3,
00310 L4RE_KEY_FN             = 0x1d0,
00311 L4RE_KEY_FN_ESC        = 0x1d1,
00312 L4RE_KEY_FN_F1        = 0x1d2,
00313 L4RE_KEY_FN_F2        = 0x1d3,
00314 L4RE_KEY_FN_F3        = 0x1d4,
00315 L4RE_KEY_FN_F4        = 0x1d5,
00316 L4RE_KEY_FN_F5        = 0x1d6,
00317 L4RE_KEY_FN_F6        = 0x1d7,
00318 L4RE_KEY_FN_F7        = 0x1d8,
00319 L4RE_KEY_FN_F8        = 0x1d9,
```

```

00320     L4RE_KEY_FN_F9           = 0x1da,
00321     L4RE_KEY_FN_F10          = 0x1db,
00322     L4RE_KEY_FN_F11          = 0x1dc,
00323     L4RE_KEY_FN_F12          = 0x1dd,
00324     L4RE_KEY_FN_1            = 0x1de,
00325     L4RE_KEY_FN_2            = 0x1df,
00326     L4RE_KEY_FN_D            = 0x1e0,
00327     L4RE_KEY_FN_E            = 0x1e1,
00328     L4RE_KEY_FN_F            = 0x1e2,
00329     L4RE_KEY_FN_S            = 0x1e3,
00330     L4RE_KEY_FN_B            = 0x1e4,
00331     L4RE_KEY_MAX              = 0x1ff,
00332 };
00333
00334 enum L4Re_events_rel
00335 {
00336     L4RE_REL_X                = 0x00,
00337     L4RE_REL_Y                = 0x01,
00338     L4RE_REL_Z                = 0x02,
00339     L4RE_REL_RX               = 0x03,
00340     L4RE_REL_RY               = 0x04,
00341     L4RE_REL_RZ               = 0x05,
00342     L4RE_REL_HWHEEL           = 0x06,
00343     L4RE_REL_DIAL             = 0x07,
00344     L4RE_REL_WHEEL            = 0x08,
00345     L4RE_REL_MISC             = 0x09,
00346     L4RE_REL_MAX              = 0x0f,
00347 };
00348
00349 enum L4Re_events_snd
00350 {
00351     L4RE_SND_CLICK             = 0x00,
00352     L4RE_SND_BELL             = 0x01,
00353     L4RE_SND_TONE             = 0x02,
00354     L4RE_SND_MAX              = 0x07,
00355 };
00356
00357 enum L4Re_events_rep
00358 {
00359     L4RE_REP_DELAY            = 0x00,
00360     L4RE_REP_PERIOD           = 0x01,
00361     L4RE_REP_MAX              = 0x01,
00362 };
00363
00364 enum L4Re_events_led
00365 {
00366     L4RE_LED_NUML             = 0x00,
00367     L4RE_LED_CAPSL            = 0x01,
00368     L4RE_LED_SCROLLLL         = 0x02,
00369     L4RE_LED_COMPOSE          = 0x03,
00370     L4RE_LED_KANA             = 0x04,
00371     L4RE_LED_SLEEP            = 0x05,
00372     L4RE_LED_SUSPEND          = 0x06,
00373     L4RE_LED_MUTE             = 0x07,
00374     L4RE_LED_MISC             = 0x08,
00375     L4RE_LED_MAIL             = 0x09,
00376     L4RE_LED_CHARGING         = 0x0a,
00377     L4RE_LED_MAX              = 0x0f,
00378 };
00379
00380 enum L4Re_events_btn
00381 {
00382     L4RE_BTN_MISC              = 0x100,
00383     L4RE_BTN_0                 = 0x100,
00384     L4RE_BTN_1                 = 0x101,
00385     L4RE_BTN_2                 = 0x102,
00386     L4RE_BTN_3                 = 0x103,
00387     L4RE_BTN_4                 = 0x104,
00388     L4RE_BTN_5                 = 0x105,
00389     L4RE_BTN_6                 = 0x106,
00390     L4RE_BTN_7                 = 0x107,
00391     L4RE_BTN_8                 = 0x108,
00392     L4RE_BTN_9                 = 0x109,
00393     L4RE_BTN_MOUSE             = 0x110,
00394     L4RE_BTN_LEFT              = 0x110,
00395     L4RE_BTN_RIGHT             = 0x111,
00396     L4RE_BTN_MIDDLE            = 0x112,
00397     L4RE_BTN_SIDE              = 0x113,
00398     L4RE_BTN_EXTRA             = 0x114,
00399     L4RE_BTN_FORWARD           = 0x115,
00400     L4RE_BTN_BACK              = 0x116,
00401     L4RE_BTN_TASK              = 0x117,
00402     L4RE_BTN_JOYSTICK          = 0x120,
00403     L4RE_BTN_TRIGGER           = 0x120,
00404     L4RE_BTN_THUMB             = 0x121,
00405     L4RE_BTN_THUMB2            = 0x122,
00406     L4RE_BTN_TOP               = 0x123,

```

```

00407     L4RE_BTN_TOP2           = 0x124,
00408     L4RE_BTN_PINKIE         = 0x125,
00409     L4RE_BTN_BASE          = 0x126,
00410     L4RE_BTN_BASE2          = 0x127,
00411     L4RE_BTN_BASE3          = 0x128,
00412     L4RE_BTN_BASE4          = 0x129,
00413     L4RE_BTN_BASE5          = 0x12a,
00414     L4RE_BTN_BASE6          = 0x12b,
00415     L4RE_BTN_DEAD          = 0x12f,
00416     L4RE_BTN_GAMEPAD        = 0x130,
00417     L4RE_BTN_A              = 0x130,
00418     L4RE_BTN_B              = 0x131,
00419     L4RE_BTN_C              = 0x132,
00420     L4RE_BTN_X              = 0x133,
00421     L4RE_BTN_Y              = 0x134,
00422     L4RE_BTN_Z              = 0x135,
00423     L4RE_BTN_TL             = 0x136,
00424     L4RE_BTN_TR             = 0x137,
00425     L4RE_BTN_TL2           = 0x138,
00426     L4RE_BTN_TR2           = 0x139,
00427     L4RE_BTN_SELECT        = 0x13a,
00428     L4RE_BTN_START          = 0x13b,
00429     L4RE_BTN_MODE           = 0x13c,
00430     L4RE_BTN_THUMBL         = 0x13d,
00431     L4RE_BTN_THUMBR         = 0x13e,
00432     L4RE_BTN_DIGI           = 0x140,
00433     L4RE_BTN_TOOL_PEN       = 0x140,
00434     L4RE_BTN_TOOL_RUBBER    = 0x141,
00435     L4RE_BTN_TOOL_BRUSH     = 0x142,
00436     L4RE_BTN_TOOL_PENCIL    = 0x143,
00437     L4RE_BTN_TOOL_AIRBRUSH  = 0x144,
00438     L4RE_BTN_TOOL_FINGER    = 0x145,
00439     L4RE_BTN_TOOL_MOUSE     = 0x146,
00440     L4RE_BTN_TOOL_LENS      = 0x147,
00441     L4RE_BTN_TOUCH          = 0x14a,
00442     L4RE_BTN_STYLUS         = 0x14b,
00443     L4RE_BTN_STYLUS2        = 0x14c,
00444     L4RE_BTN_TOOL_DOUBLETAP = 0x14d,
00445     L4RE_BTN_TOOL_TRIPLETAP = 0x14e,
00446     L4RE_BTN_WHEEL          = 0x150,
00447     L4RE_BTN_GEAR_DOWN      = 0x150,
00448     L4RE_BTN_GEAR_UP        = 0x151,
00449 };
00450
00451 enum L4Re_events_sw
00452 {
00453     L4RE_SW_0      = 0x00,
00454     L4RE_SW_1      = 0x01,
00455     L4RE_SW_2      = 0x02,
00456     L4RE_SW_3      = 0x03,
00457     L4RE_SW_4      = 0x04,
00458     L4RE_SW_5      = 0x05,
00459     L4RE_SW_6      = 0x06,
00460     L4RE_SW_7      = 0x07,
00461     L4RE_SW_MAX    = 0x0f,
00462 };
00463
00464 enum L4Re_events_ev
00465 {
00466     L4RE_EV_SYN      = 0x00,
00467     L4RE_EV_KEY       = 0x01,
00468     L4RE_EV_REL       = 0x02,
00469     L4RE_EV_ABS       = 0x03,
00470     L4RE_EV_MSC       = 0x04,
00471     L4RE_EV_SW        = 0x05,
00472     L4RE_EV_LED       = 0x11,
00473     L4RE_EV_SND       = 0x12,
00474     L4RE_EV_REP       = 0x14,
00475     L4RE_EV_FF        = 0x15,
00476     L4RE_EV_PWR       = 0x16,
00477     L4RE_EV_FF_STATUS = 0x17,
00478     L4RE_EV_WINDOW    = 0x18,
00479     L4RE_EV_PM         = 0x1e, // power management signals
00480     L4RE_EV_MAX        = 0x1f,
00481 };
00482
00483 enum L4Re_events_syn
00484 {
00485     L4RE_SYN_REPORT    = 0,
00486     L4RE_SYN_CONFIG    = 1,
00487     L4RE_SYN_MT_REPORT = 2,
00488
00489     L4RE_SYN_STREAM_CFG = 0x80,
00490 };
00491
00492 enum L4Re_stream_cfg
00493 {

```

```

00494     L4RE_SYN_STREAM_NEW    = 0,
00495     L4RE_SYN_STREAM_CLOSE = 1,
00496 };
00497
00498 enum L4Re_events_abs
00499 {
00500     L4RE_ABS_X                = 0x00,
00501     L4RE_ABS_Y                = 0x01,
00502     L4RE_ABS_Z                = 0x02,
00503     L4RE_ABS_RX               = 0x03,
00504     L4RE_ABS_RY               = 0x04,
00505     L4RE_ABS_RZ               = 0x05,
00506     L4RE_ABS_THROTTLE         = 0x06,
00507     L4RE_ABS_RUDDER           = 0x07,
00508     L4RE_ABS_WHEEL            = 0x08,
00509     L4RE_ABS_GAS               = 0x09,
00510     L4RE_ABS_BRAKE             = 0x0a,
00511     L4RE_ABS_HAT0X            = 0x10,
00512     L4RE_ABS_HAT0Y            = 0x11,
00513     L4RE_ABS_HAT1X            = 0x12,
00514     L4RE_ABS_HAT1Y            = 0x13,
00515     L4RE_ABS_HAT2X            = 0x14,
00516     L4RE_ABS_HAT2Y            = 0x15,
00517     L4RE_ABS_HAT3X            = 0x16,
00518     L4RE_ABS_HAT3Y            = 0x17,
00519     L4RE_ABS_PRESSURE          = 0x18,
00520     L4RE_ABS_DISTANCE          = 0x19,
00521     L4RE_ABS_TILT_X           = 0x1a,
00522     L4RE_ABS_TILT_Y           = 0x1b,
00523     L4RE_ABS_TOOL_WIDTH       = 0x1c,
00524     L4RE_ABS_VOLUME           = 0x20,
00525     L4RE_ABS_MISC              = 0x28,
00526     L4RE_ABS_MT_TOUCH_MAJOR    = 0x30,
00527     L4RE_ABS_MT_TOUCH_MINOR    = 0x31,
00528     L4RE_ABS_MT_WIDTH_MAJOR    = 0x32,
00529     L4RE_ABS_MT_WIDTH_MINOR    = 0x33,
00530     L4RE_ABS_MT_ORIENTATION    = 0x34,
00531     L4RE_ABS_MT_POSITION_X     = 0x35,
00532     L4RE_ABS_MT_POSITION_Y     = 0x36,
00533     L4RE_ABS_MT_TOOL_TYPE      = 0x37,
00534     L4RE_ABS_MT_BLOB_ID        = 0x38,
00535     L4RE_ABS_MT_TRACKING_ID     = 0x39,
00536     L4RE_ABS_MT_PRESSURE       = 0x3a,
00537     L4RE_ABS_MT_DISTANCE       = 0x3b,
00538
00539     L4RE_ABS_MAX                = 0x3f,
00540 };
00541
00542 enum L4Re_events_msc
00543 {
00544     L4RE_MSC_SERIAL            = 0x00,
00545     L4RE_MSC_PULSELED          = 0x01,
00546     L4RE_MSC_GESTURE           = 0x02,
00547     L4RE_MSC_RAW                = 0x03,
00548     L4RE_MSC_SCAN              = 0x04,
00549     L4RE_MSC_MAX                = 0x07,
00550 };
00551
00552 enum L4Re_events_properties
00553 {
00554     L4RE_EVENT_PROP_POINTER     = 0x00,
00555     L4RE_EVENT_PROP_DIRECT      = 0x01,
00556     L4RE_EVENT_PROP_BUTTONPAD   = 0x02,
00557     L4RE_EVENT_PROP_SEMI_MT     = 0x03,
00558     //L4RE_EVENT_PROP_MAX        = 0x1f
00559 };

```

## 16.327 l4/re/impl/dataspace\_impl.h File Reference

Dataspace client stub implementation.

```

#include <l4/re/dataspace>
#include <l4/sys/cxx/ipc_client>
#include <l4/sys/cxx/consts>

```



```

00023 namespace L4Re {
00024
00025     l4_ret_t
00026     Dataspace::__map(Dataspace::Offset offset, unsigned char *size,
00027                     Dataspace::Flags flags,
00028                     Dataspace::Map_addr local_addr,
00029                     L4::Cap<L4::Task> dst) const noexcept
00030     {
00031         Map_addr spot = local_addr & ~(~0ULL « L4_umword_t(*size));
00032         Map_addr base = local_addr & (~0ULL « L4_umword_t(*size));
00033         L4::Ipc::Rcv_fpage r = L4::Ipc::Rcv_fpage::mem(base, *size, 0, dst);
00034
00035         L4::Ipc::Snd_fpage fp;
00036         l4_ret_t err = map_t::call(c(), offset, spot, flags, r, fp, l4_utcb());
00037         if (L4_UNLIKELY(err < 0))
00038             return err;
00039
00040         *size = fp.rcv_order();
00041         return err;
00042     }
00043
00044     l4_ret_t
00045     Dataspace::map_region(Dataspace::Offset offset, Dataspace::Flags flags,
00046                           Dataspace::Map_addr min_addr,
00047                           Dataspace::Map_addr max_addr,
00048                           L4::Cap<L4::Task> dst) const noexcept
00049     {
00050         min_addr = L4::trunc_page(min_addr);
00051         max_addr = L4::round_page(max_addr);
00052         unsigned char order = L4_LOG2_PAGESIZE;
00053
00054         l4_ret_t err = 0;
00055
00056         while (min_addr < max_addr)
00057         {
00058             unsigned char order_mapped;
00059             order_mapped = order
00060                 = L4::max_order(order, min_addr, min_addr, max_addr, min_addr);
00061
00062             err = __map(offset, &order_mapped, flags, min_addr, dst);
00063             if (L4_UNLIKELY(err < 0))
00064                 return err;
00065
00066             if (order > order_mapped)
00067                 order = order_mapped;
00068
00069             min_addr += Map_addr(1) « order;
00070             offset += Map_addr(1) « order;
00071
00072             if (min_addr >= max_addr)
00073                 return 0;
00074
00075             while (min_addr != L4::trunc_order(min_addr, order)
00076                 || max_addr < L4::round_order(min_addr + 1, order))
00077                 --order;
00078         }
00079
00080         return 0;
00081     }
00082
00083     l4_ret_t
00084     Dataspace::map(Dataspace::Offset offset, Dataspace::Flags flags,
00085                    Dataspace::Map_addr local_addr,
00086                    Dataspace::Map_addr min_addr,
00087                    Dataspace::Map_addr max_addr,
00088                    L4::Cap<L4::Task> dst) const noexcept
00089     {
00090         min_addr = L4::trunc_page(min_addr);
00091         max_addr = L4::round_page(max_addr);
00092         local_addr = L4::trunc_page(local_addr);
00093         unsigned char order
00094             = L4::max_order(L4_LOG2_PAGESIZE, local_addr, min_addr, max_addr, local_addr);
00095
00096         return __map(offset, &order, flags, local_addr, dst);
00097     }
00098
00099     Dataspace::Size
00100     Dataspace::size() const noexcept
00101     {
00102         Stats stats = Stats();
00103
00104         int err = info(&stats);
00105         if (err < 0)
00106             return 0;
00107
00108         return stats.size;
00109     }

```

```

00110
00111 Dataspace::Flags
00112 Dataspace::flags() const noexcept
00113 {
00114     Stats stats = Stats();
00115
00116     int err = info(&stats);
00117     if (err < 0)
00118         return Flags(0);
00119
00120     return stats.flags;
00121 }
00122
00123 };

```

## 16.329 l4/re/impl/mem\_alloc\_impl.h File Reference


Memory allocator client stub implementation.

```

#include <l4/re/mem_alloc>
#include <l4/re/mem_alloc-sys.h>
#include <l4/re/dataspace>
#include <l4/re/error_helper>
#include <l4/sys/factory>

```

Include dependency graph for mem\_alloc\_impl.h:



### Namespaces

- namespace [L4Re](#)  
[L4Re C++ Interfaces](#).

### 16.329.1 Detailed Description

Memory allocator client stub implementation.

Definition in file [mem\\_alloc\\_impl.h](#).

## 16.330 mem\_alloc\_impl.h

[Go to the documentation of this file.](#)

```

00001
00005 /*
00006  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00007  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00008  *      economic rights: Technische Universität Dresden (Germany)
00009  *
00010  * License: see LICENSE.spdx (in this directory or the directories above)
00011  */
00012 #include <l4/re/mem_alloc>
00013 #include <l4/re/mem_alloc-sys.h>
00014 #include <l4/re/dataspace>
00015 #include <l4/re/error_helper>
00016
00017 #include <l4/sys/factory>
00018
00019
00020 namespace L4Re
00021 {
00022
00023     l4_ret_t
00024     Mem_alloc::alloc(long size,
00025                     L4::Cap<Dataspace> mem, unsigned long flags,
00026                     unsigned long align, l4_addr_t paddr) const noexcept
00027     {
00028         L4::Cap<L4::Factory> f(cap());
00029         auto call = f->create(mem, L4Re::Dataspace::Protocol);
00030         call « l4_mword_t(size)
00031             « l4_umword_t(flags)
00032             « l4_umword_t(align);
00033         if (flags & Fixed_paddr)
00034             call « l4_umword_t(paddr);
00035         return l4_error(call);
00036     }
00037
00038 };

```

## 16.331 l4/re/impl/namespace\_impl.h File Reference

Namespace client stub implementation.

```

#include <l4/re/namespace>
#include <l4/util/util.h>
#include <l4/sys/cxx/ipc_client>
#include <l4/sys/assert.h>
#include <string.h>

```



[illegible]

- namespace **L4Re**  
*L4Re C++ Interfaces.*

Definition in file [namespace impl.h](#).

[Go to the documentation of this file.](#)

```
00001
00002 /*
00003  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00004  * Alexander Warg <warg@os.inf.tu-dresden.de>
00005  * economic rights: Technische Universität Dresden (Germany)
00006  *
00007  * License: see LICENSE.spdx (in this directory or the directories above)
00008  */
00009 #include <l4/re/namespace>
00010
00011 #include <l4/util/util.h>
00012
00013 #include <l4/sys/cxx/ipc_client>
00014
00015 #include <l4/sys/assert.h>
00016
00017 #include <string.h>
00018
00019
00020 L4_RPC_DEF(L4Re::Namespace::query);
```

```

00021 L4_RPC_DEF(L4Re::Namespace::register_obj);
00022 L4_RPC_DEF(L4Re::Namespace::unlink);
00023
00024 namespace L4Re {
00025
00026     l4_ret_t
00027     Namespace::_query(char const *name, unsigned len,
00028                       L4::Cap<void> const &target,
00029                       l4_umword_t *local_id, bool iterate) const noexcept
00030     {
00031         l4_assert(target.is_valid());
00032
00033         L4::Cap<Namespace> ns = c();
00034         L4::Ipc::Array<char const, unsigned long> _name(len, name);
00035
00036         while (_name.length > 0)
00037         {
00038             L4::Ipc::Snd_fpage cap;
00039             L4::Opcode dummy;
00040             int err = query_t::call(ns, _name,
00041                                   L4::Ipc::Small_buf(target.cap(),
00042                                                         local_id
00043                                                         ? L4_RCV_ITEM_LOCAL_ID
00044                                                         : 0),
00045                                   cap, dummy, _name);
00046             if (err < 0)
00047                 return err;
00048
00049             bool const partly = err & Partly_resolved;
00050             if (cap.id_received())
00051             {
00052                 *local_id = cap.data();
00053                 return _name.length;
00054             }
00055
00056             if (partly && iterate)
00057                 ns = L4::cap_cast<Namespace>(target);
00058             else
00059                 return err;
00060         }
00061
00062         return _name.length;
00063     }
00064
00065     l4_ret_t
00066     Namespace::query(char const *name, unsigned len, L4::Cap<void> const &target,
00067                     int timeout, l4_umword_t *local_id, bool iterate) const noexcept
00068     {
00069         if (L4_UNLIKELY(len == 0))
00070             return -L4_EINVAL;
00071
00072         if (L4_UNLIKELY(timeout < 0))
00073             return -L4_EINVAL;
00074
00075         l4_ret_t ret;
00076         long rem = timeout;
00077         long to = 0;
00078
00079         if (rem)
00080             to = 10;
00081
00082         do
00083         {
00084             ret = _query(name, len, target, local_id, iterate);
00085
00086             if (ret >= 0)
00087                 return ret;
00088
00089             if (L4_UNLIKELY(ret != -L4_EAGAIN))
00090                 return ret;
00091
00092             if (rem == to)
00093                 return ret;
00094
00095             l4_sleep(to);
00096
00097             if (rem > 0)
00098             {
00099                 rem -= to;
00100                 if (rem < 0)
00101                 {
00102                     to = rem = 0;
00103                     continue; // one final try
00104                 }
00105             }
00106
00107             if (to < 100)

```

```

00108         to += to;
00109     }
00110     while (486);
00111 }
00112
00113 l4_ret_t
00114 Namespace::query(char const *name, L4::Cap<void> const &target,
00115                 int timeout, l4_umword_t *local_id,
00116                 bool iterate) const noexcept
00117 {
00118     return query(name, __builtin_strlen(name), target,
00119                 timeout, local_id, iterate);
00120 }
00121
00122 }

```

## 16.333 l4/re/impl/rm\_impl.h File Reference


Region map client stub implementation.

```

#include <l4/bid_config.h>
#include <l4/re/rm>
#include <l4/re/dataspace>
#include <l4/sys/cxx/ipc_client>
#include <l4/sys/task>
#include <l4/sys/err.h>

```

Include dependency graph for rm\_impl.h:



### Namespaces

- namespace [L4Re](#)  
*L4Re C++ Interfaces.*

### 16.333.1 Detailed Description

Region map client stub implementation.

Definition in file [rm\\_impl.h](#).

## 16.334 rm\_impl.h

[Go to the documentation of this file.](#)

```

00001
00005 /*
00006  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00007  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00008  *      economic rights: Technische Universität Dresden (Germany)
00009  *
00010  * License: see LICENSE.spdx (in this directory or the directories above)
00011  */
00012
00013 #include <l4/bid_config.h>
00014 #include <l4/re/rm>
00015 #include <l4/re/dataspace>
00016
00017 #include <l4/sys/cxx/ipc_client>
00018
00019 #include <l4/sys/task>
00020 #include <l4/sys/err.h>
00021
00022 L4_RPC_DEF(L4Re::Rm::reserve_area);
00023 L4_RPC_DEF(L4Re::Rm::free_area);
00024 L4_RPC_DEF(L4Re::Rm::attach);
00025 L4_RPC_DEF(L4Re::Rm::detach);
00026 L4_RPC_DEF(L4Re::Rm::get_regions);
00027 L4_RPC_DEF(L4Re::Rm::get_areas);
00028 L4_RPC_DEF(L4Re::Rm::find);
00029 L4_RPC_DEF(L4Re::Rm::get_info);
00030
00031 namespace L4Re
00032 {
00033
00034     l4_ret_t
00035     Rm::attach(l4_addr_t *start, unsigned long size, Rm::Flags flags,
00036               L4::Ipc::Cap<Dataspace> mem, Rm::Offset offs,
00037               unsigned char align, L4::Cap<L4::Task> const task,
00038               char const *name, Rm::Offset backing_offset) const noexcept
00039     {
00040         if ((flags & F::Rights_mask) == Flags(0)
00041             || (flags & (F::Reserved | F::Kernel)))
00042             mem = L4::Ipc::Cap<L4Re::Dataspace>();
00043
00044         char const n = '\0';
00045         l4_ret_t e = attach_t::call(c(), start, size, flags, mem, offs, align,
00046                                    mem.cap().cap(), name ? name : &n, backing_offset);
00047         if (e < 0)
00048             return e;
00049
00050 #ifdef CONFIG_MMU
00051         if ((flags & (F::Eager_map | F::No_eager_map)) == F::Eager_map)
00052             #else
00053             if (!(flags & F::No_eager_map) && mem.is_valid())
00054             #endif
00055                 e = mem.cap()->map_region(offs, flags.map_flags(), *start, *start + size,
00056                                           task);
00057
00058         return e;
00059     }
00060
00061     l4_ret_t
00062     Rm::detach(l4_addr_t start, unsigned long size, L4::Cap<Dataspace> *mem,
00063               L4::Cap<L4::Task> task, unsigned flags) const noexcept
00064     {
00065         l4_addr_t rstart = 0, rsize = 0;
00066         l4_cap_idx_t mem_cap = L4_INVALID_CAP;
00067         l4_ret_t e = detach_t::call(c(), start, size, flags, rstart, rsize, mem_cap);
00068         if (L4_UNLIKELY(e < 0))
00069             return e;
00070
00071         if (mem)
00072             *mem = L4::Cap<L4Re::Dataspace>(mem_cap);
00073
00074         if (!task.is_valid())
00075             return e;
00076
00077         rsize = l4_round_page(rsize);
00078         unsigned order = L4_LOG2_PAGESIZE;
00079         unsigned long sz = (1UL << order);
00080         for (unsigned long p = rstart; rsize; p += sz, rsize -= sz)
00081         {
00082             while (sz > rsize)
00083             {
00084                 --order;
00085                 sz >>= 1;

```

```

00086     }
00087
00088     for (;;)
00089     {
00090         unsigned long m = sz << 1;
00091         if (m > rsize)
00092             break;
00093
00094         if (p & (m - 1))
00095             break;
00096
00097         ++order;
00098         sz <= 1;
00099     }
00100
00101     task->unmap(l4_fpage(p, order, L4_FPAGE_RWX),
00102                L4_FP_ALL_SPACES);
00103 }
00104
00105 return e;
00106 }
00107
00108 }

```

## 16.335 inhibitor

```

00001 // vim:set ft=cpp: -*- Mode: C++ -*-
00002 /*
00003  * (c) 2014 Steffen Liebergeld <steffen.liebergeld@kernkonzept.com>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007 #pragma once
00008
00009 #include <l4/sys/capability>
00010 #include <l4/sys/cxx/ipc_iface>
00011 #include <l4/sys/cxx/ipc_string>
00012 #include <l4/re/protocols.h>
00013
00014 namespace L4Re {
00015
00038 class Inhibitor :
00039     public L4::Kobject_t<Inhibitor, L4::Kobject, L4RE_PROTO_INHIBITOR>
00040 {
00041 public:
00042     enum
00043     {
00044         Name_max = 20
00045     };
00046
00057 L4_INLINE_RPC(l4_ret_t, acquire, (l4_umword_t id, L4::Ipc::String<> reason));
00058
00067 L4_INLINE_RPC(l4_ret_t, release, (l4_umword_t id));
00068
00084 l4_ret_t next_lock_info(char *name, unsigned len, l4_mword_t current_id = -1,
00085                        l4_utcb_t *utcb = l4_utcb())
00086 {
00087     L4::Ipc::String<char> name_buf(len, name);
00088     l4_ret_t r = next_lock_info_t::call(c(), &current_id, name_buf, utcb);
00089     if (r < 0)
00090         return r;
00091
00092     return current_id;
00093 }
00094
00095 L4_INLINE_RPC_NF(l4_ret_t, next_lock_info, (L4::Ipc::In_out<l4_mword_t *> current_id,
00096                                             L4::Ipc::String<char> &name));
00097
00098 typedef L4::Typeid::Rpcs<acquire_t, release_t, next_lock_info_t> Rpcs;
00099 };
00100
00101 }

```

## 16.336 inhibitor-sys.h

```

00001 /*
00002  * (c) 2014 Steffen Liebergeld <steffen.liebergeld@kernkonzept.com>
00003  *

```

```

00004  * License: see LICENSE.spdx (in this directory or the directories above)
00005  */
00006  #pragma once
00007
00008  namespace L4Re {
00009      namespace Inhibitor_ {
00015          enum Opcodes { Acquire, Release, Next_lock_info };
00016      }
00017  }

```

## 16.337 itas

```

00001  // vi:set ft=cpp: -- Mode: C++ --
00002  /*
00003   * Copyright (C) 2025 Kernkonzept GmbH.
00004   * Author(s): Jan Klötzke <jan.kloetzke@kernkonzept.com>
00005   *
00006   * License: see LICENSE.spdx (in this directory or the directories above)
00007   */
00008
00009  #pragma once
00010
00011  #include <l4/sys/cxx/ipc_iface>
00012  #include <l4/sys/cxx/ipc_types>
00013  #include <l4/sys/cxx/types>
00014  #include <l4/sys/l4int.h>
00015  #include <l4/sys/thread>
00016  #include <l4/sys/types.h>
00017
00018  #include <signal.h>
00019  #include <sys/time.h>
00020
00021  namespace L4Re
00022  {
00023
00030  class L4_EXPORT Itas :
00031      public L4::Kobject_t<Itas, L4::Kobject,
00032                          L4RE_PROTO_ITAS,
00033                          L4::Type_info::Demand_t<2> >
00034  {
00035  public:
00048      L4_INLINE_RPC(int, register_thread, (L4::Ipc::Cap<L4::Thread> parent,
00049                                          L4::Ipc::Cap<L4::Thread> thread_cap,
00050                                          l4_addr_t thread_utcb));
00051
00060      L4_INLINE_RPC(int, unregister_thread, (L4::Ipc::Cap<L4::Thread> thread));
00061
00062      // sigaction.sa_flags is usually `unsigned long`, except for MIPS...
00063      enum : unsigned
00064      {
00065          Ignore_sigaction = ~0U
00066      };
00067
00079      L4_INLINE_RPC(int, sigaction, (int signum,
00080                                   const struct sigaction *act,
00081                                   struct sigaction *oldact));
00082
00095      L4_INLINE_RPC(int, sigaltstack, (L4::Ipc::Cap<L4::Thread> thread,
00096                                      const struct sigaltstack *ss,
00097                                      struct sigaltstack *oss));
00098
00113      L4_INLINE_RPC(int, sigprocmask, (L4::Ipc::Cap<L4::Thread> thread,
00114                                      int how, sigset_t const *set,
00115                                      sigset_t *oldset));
00116
00126      L4_INLINE_RPC(int, sigpending, (L4::Ipc::Cap<L4::Thread> thread,
00127                                     sigset_t *set));
00128
00138      L4_INLINE_RPC(int, setitimer, (int which,
00139                                    const struct itimerval *new_value,
00140                                    struct itimerval *old_value));
00141
00150      L4_INLINE_RPC(int, getitimer, (int which, struct itimerval *curr_value));
00151
00158      L4_INLINE_RPC(int, raise, (L4::Ipc::Cap<L4::Thread> thread, int sig));
00159
00160      typedef L4::Typeid::Rpc<
00161          register_thread_t, unregister_thread_t, sigaction_t, sigaltstack_t,
00162          sigprocmask_t, sigpending_t, setitimer_t, getitimer_t, raise_t
00163      > Rpc<
00164      >;
00165
00166  }


```

## 16.338 l4/re/l4aux.h File Reference

Auxiliary definitions.

```
#include <l4/sys/types.h>
```

Include dependency graph for l4aux.h:



### Data Structures

- struct [l4re\\_aux\\_t](#)  
*Auxiliary descriptor.*

### Typedefs

- typedef struct l4re\_aux\_t [l4re\\_aux\\_t](#)  
*Auxiliary descriptor.*

### Enumerations

- enum [l4re\\_aux\\_ldr\\_flags\\_t](#)  
*Flags for program loading.*

### 16.338.1 Detailed Description


Auxiliary definitions.

Definition in file [l4aux.h](#).





This graph shows which files directly or indirectly include this file:



## Data Structures

- class [L4Re::Log](#)  
*Log interface class.*

## Namespaces

- namespace [L4Re](#)  
*L4Re C++ Interfaces.*

### 16.340.1 Detailed Description

Log interface.

Definition in file [log](#).

## 16.341 log

[Go to the documentation of this file.](#)

```
00001 // -*- Mode: C++ -*-
00002 // vim:ft=cpp
00007 /*
00008  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00009  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00010  *      economic rights: Technische Universität Dresden (Germany)
00011  *
00012  * License: see LICENSE.spdx (in this directory or the directories above)
00013  */
00014 #pragma once
00015
00016 #include <14/sys/vcon>
00017
00018 namespace L4Re {
00019
00033 class L4_EXPORT Log : public L4::Kobject_t<Log, L4::Vcon, L4::PROTO_EMPTY>
00034 {
00035 public:
00036
00043 void printn(char const *string, int len) const noexcept;
00044
00050 void print(char const *string) const noexcept;
00051 };
00052 }
```

## 16.342 l4/re/log-sys.h File Reference

Log protocol definition.

### Namespaces

- namespace [L4Re](#)  
*[L4Re](#) C++ Interfaces.*

### Enumerations

- enum [L4Re::Log\\_::Opcodes](#)  
*Logging-service communication-protocol opcodes.*

### 16.342.1 Detailed Description

Log protocol definition.

Definition in file [log-sys.h](#).

## 16.343 log-sys.h

[Go to the documentation of this file.](#)

```

00001
00005 /*
00006  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00007  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00008  *      economic rights: Technische Universität Dresden (Germany)
00009  *
00010  * License: see LICENSE.spdx (in this directory or the directories above)
00011  */
00012 #pragma once
00013
00014 namespace L4Re
00015 {
00016     namespace Log_
00017     {
00023         enum Opcodes { Print };
00024     };
00025 };

```

## 16.344 l4/re/mem\_alloc File Reference


Memory allocator interface.

```


#include <l4/re/protocols.h>
#include <l4/sys/capability>
#include <l4/sys/cxx/ipc_iface>

```

Include dependency graph for mem\_alloc:



This graph shows which files directly or indirectly include this file:



## Data Structures

- class `L4Re::Mem_alloc`  
*Memory allocation interface.*
- struct `L4Re::Mem_alloc::Stats`  
*Statistics about memory-allocator.*

## Namespaces

- namespace **L4Re**  
*L4Re C++ Interfaces.*

## 16.344.1 Detailed Description

Memory allocator interface.

Definition in file [mem\\_alloc](#).

## 16.345 mem\_alloc


[Go to the documentation of this file.](#)

```
00001 // -*- Mode: C++ -*-
00002 // vim:ft=cpp
00007 /*
00008  * Copyright (C) 2014-2016, 2019, 2021, 2024-2025 Kernkonzept GmbH.
00009  * Author(s): Alexander Warg <alexander.warg@kernkonzept.com>
00010  */
00011 /*
00012  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00013  *           Alexander Warg <warg@os.inf.tu-dresden.de>,
00014  *           Torsten Frenzel <frenzel@os.inf.tu-dresden.de>
00015  *           economic rights: Technische Universität Dresden (Germany)
00016  *
00017  * License: see LICENSE.spdx (in this directory or the directories above)
00018  */
00019 #pragma once
00020
00021 #include <l4/re/protocols.h>
00022 #include <l4/sys/capability>
00023 #include <l4/sys/cxx/ipc_iface>
00024 #include <l4/sys/factory>
00025
00026 namespace L4Re {
00027 class Dataspace;
00028
00029 // MISSING:
00030 // * alignment constraints
00031 // * shall we support superpages in noncont memory?
00032
00052 class L4_EXPORT Mem_alloc :
00053 public L4::Kobject_t<Mem_alloc, L4::Factory, L4RE_PROTO_MEM_ALLOC>
00054 {
00055 public:
00062 enum Mem_alloc_flags
00063 {
00064     Continuous    = 0x01,
00065     Pinned        = 0x02,
00066     Super_pages   = 0x04,
00067     Fixed_paddr   = 0x08,
00069 };
00070
00074 struct Stats
00075 {
00083     l4_size_t quota;
00084
00094     l4_size_t quota_used;
00095
00102     l4_size_t mem_limit;
00103
00116     l4_size_t mem_used;
00117
00126     l4_size_t mem_free;
00127 };
00128
00157 l4_ret_t alloc(long size, L4::Cap<Dataspace> mem,
00158               unsigned long flags = 0, unsigned long align = 0,
00159               l4_addr_t paddr = 0) const noexcept;
00160
00169 L4_INLINE_RPC(long, info, (Stats &stats));
00170
00171 typedef L4::Typeid::Rpc<info_t> Rpc;
00172 };
00173
00174 };
```

## 16.346 l4/re/mem\_alloc-sys.h File Reference

Memory allocator protocol definitions.

This graph shows which files directly or indirectly include this file:



### Namespaces

- namespace [L4Re](#)  
*L4Re C++ Interfaces.*

### Enumerations

- enum [L4Re::Mem\\_alloc\\_::Opcodes](#)  
*Memory-allocator communication-protocol opcodes.*

### 16.346.1 Detailed Description

Memory allocator protocol definitions.

Definition in file [mem\\_alloc-sys.h](#).

## 16.347 mem\_alloc-sys.h

[Go to the documentation of this file.](#)

```

00001
00005 /*
00006  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00007  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00008  *      economic rights: Technische Universität Dresden (Germany)
00009  *
00010  * License: see LICENSE.spdx (in this directory or the directories above)
00011  */
00012 #pragma once
00013
00014 namespace L4Re
00015 {
00016     namespace Mem_alloc_
00017     {
00023         enum Opcodes { Alloc, Free };
00024     };
00025 };
  
```



## 16.349 mmio\_space

[Go to the documentation of this file.](#)

```

00001 // -*- Mode: C++ -*-
00002 // vim:ft=cpp
00003 /*
00004  * Copyright (C) 2017-2018, 2022, 2024 Kernkonzept GmbH.
00005  * Author(s): Sarah Hoffmann <sarah.hoffmann@kernkonzept.com>
00006  *
00007  * License: see LICENSE.spdx (in this directory or the directories above)
00008  */
00013 #pragma once
00014
00015 #include <l4/re/protocols.h>
00016 #include <l4/sys/capability>
00017 #include <l4/sys/cxx/ipc_types>
00018 #include <l4/sys/cxx/ipc_iface>
00019
00020 namespace L4Re
00021 {
00022
00045 struct L4_EXPORT Mmio_space
00046 : public L4::Kobject_t<Mmio_space, L4::Kobject, L4RE_PROTO_MMIO_SPACE>
00047 {
00049     enum Access_width
00050     {
00051         Wd_8bit = 0,
00052         Wd_16bit = 1,
00053         Wd_32bit = 2,
00054         Wd_64bit = 3
00055     };
00056
00058     typedef l4_uint64_t Addr;
00059
00074     L4_INLINE_RPC(l4_ret_t, mmio_read, (Addr addr, char width, l4_uint64_t *value));
00075
00090     L4_INLINE_RPC(l4_ret_t, mmio_write, (Addr addr, char width, l4_uint64_t value));
00091
00092     typedef L4::Typeid::Rpc<mmio_read_t, mmio_write_t> Rpc;
00093 };
00094
00095 }
```


## 16.350 l4/re/namespace File Reference

Namespace interface.


```

#include <l4/sys/capability>
#include <l4/re/protocols.h>
#include <l4/sys/cxx/ipc_iface>
#include <l4/sys/cxx/ipc_array>
#include <l4/sys/cxx/ipc_string>
```

Include dependency graph for namespace:



This graph shows which files directly or indirectly include this file:



## Data Structures

- class [L4Re::Namespace](#)  
*Name-space interface.*

## Namespaces

- namespace [L4Re](#)  
*L4Re C++ Interfaces.*



## 16.350.1 Detailed Description

Namespace interface.

Definition in file [namespace](#).

## 16.351 namespace

[Go to the documentation of this file.](#)

```

00001 // -*- Mode: C++ -*-
00002 // vim:ft=cpp
00003 /*
00008 * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00009 *      Alexander Warg <warg@os.inf.tu-dresden.de>,
00010 *      Björn Döbel <doebel@os.inf.tu-dresden.de>
00011 *      economic rights: Technische Universität Dresden (Germany)
00012 *
00013 * License: see LICENSE.spdx (in this directory or the directories above)
00014 */
00015 #pragma once
00016
00017 #include <l4/sys/capability>
00018 #include <l4/re/protocols.h>
00019 #include <l4/sys/cxx/ipc_iface>
00020 #include <l4/sys/cxx/ipc_array>
00021 #include <l4/sys/cxx/ipc_string>
00022
00023 namespace L4Re {
00024
00049 class L4_EXPORT Namespace :
00050     public L4::Kobject_t<Namespace, L4::Kobject, L4RE_PROTO_NAMESPACE,
00051         L4::Type_info::Demand_t<1> >
00052 {
00053 public:
00057     enum Register_flags
00058     {
00059         Ro      = L4_CAP_FPAGE_RO,
00060         Rw      = L4_CAP_FPAGE_RW,
00061         Rs      = L4_CAP_FPAGE_RS,
00062         Rws     = L4_CAP_FPAGE_RWS,
00063         Strong  = L4_CAP_FPAGE_S,
00064         Trusted = 0x008,
00065
00066         Cap_flags = Ro | Rw | Strong | Trusted,
00067
00068         Link      = 0x100,
00069         Overwrite = 0x200,
00070     };
00071
00077     enum Query_result_flags
00078     {
00079         Partly_resolved = 0x020,
00080     };
00081
00083     enum Query_timeout
00084     {
00085         To_default      = 3600000,
00086         To_non_blocking = 0,
00087     };
00088
00089     L4_RPC_NF(
00090         l4_ret_t, query, (L4::Ipc::Array_ref<char const, unsigned long> name,
00091             L4::Ipc::Small_buf cap,
00092             L4::Ipc::Snd_fpage &snd_cap,
00093             L4::Ipc::Opt<L4::Opcode &> dummy,
00094             L4::Ipc::Opt<
00095                 L4::Ipc::Array_ref<char const, unsigned long> &> out_name));
00096
00122     l4_ret_t query(char const *name, L4::Cap<void> const &cap,
00123         int timeout = To_default,
00124         l4_umword_t *local_id = 0, bool iterate = true) const noexcept;
00125
00135     l4_ret_t query(char const *name, unsigned len, L4::Cap<void> const &cap,
00136         int timeout = To_default,
00137         l4_umword_t *local_id = 0, bool iterate = true) const noexcept;
00138
00139     L4_RPC_NF(l4_ret_t, register_obj, (unsigned flags,
00140         L4::Ipc::Array<char const, unsigned long> name,
```

```

00141         L4::Ip<::Opt< L4::Ip<::Cap<void> > obj),
00142         L4::Ip<::Call_t<L4_CAP_FPAGE_W>);
00143
00167  l4_ret_t register_obj(char const *name, L4::Ip<::Cap<void> obj,
00168                        unsigned flags = Rw) const noexcept
00169  {
00170      return register_obj_t::call(c(), flags,
00171                                  L4::Ip<::Array<char const, unsigned long>(
00172                                      __builtin_strlen(name), name),
00173                                  obj);
00174  }
00175
00176  L4_RPC_NF_OP(3, // backward compatibility opcode
00177              l4_ret_t, unlink, (L4::Ip<::Array<char const, unsigned long> name),
00178              L4::Ip<::Call_t<L4_CAP_FPAGE_W>);
00179
00194  l4_ret_t unlink(char const* name)
00195  {
00196      return unlink_t::call(c(), L4::Ip<::Array<char const, unsigned long>(
00197                                      __builtin_strlen(name), name));
00198  }
00199
00200  typedef L4::Typeid::Rpc<query_t, register_obj_t, unlink_t> Rpc;
00201
00202 private:
00203  l4_ret_t _query(char const *name, unsigned len,
00204                 L4::Cap<void> const &target, l4_umword_t *local_id,
00205                 bool iterate) const noexcept;
00206
00207 };
00208
00209 };

```

## 16.352 I4/re/namespace-sys.h File Reference

Namespace protocol definitions.

### Namespaces

- namespace [L4Re](#)  
*L4Re C++ Interfaces.*

### Enumerations

- enum [L4Re::Namespace\\_::Opcodes](#)  
*Name-space communication-protocol opcodes.*

### 16.352.1 Detailed Description

Namespace protocol definitions.

Definition in file [namespace-sys.h](#).

## 16.353 namespace-sys.h

[Go to the documentation of this file.](#)

```


00001
00005 /*
00006  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00007  * Alexander Warg <warg@os.inf.tu-dresden.de>
00008  * economic rights: Technische Universität Dresden (Germany)
00009  *
00010  * License: see LICENSE.spdx (in this directory or the directories above)
00011  */
00012 #pragma once
00013
00014 namespace L4Re {
00015     namespace Namespace_
00016     {
00022         enum Opcodes { Query, Register, Link, Unlink };
00023     };
00024 };

```


### 16.354 I4/re/parent File Reference

Parent interface.

```
#include <l4/sys/capability>
#include <l4/re/protocols.h>
#include <l4/sys/cxx/ipc_iface>
Include dependency graph for parent:
```



This graph shows which files directly or indirectly include this file:



## Data Structures

- class [L4Re::Parent](#)  
*Parent interface.*

## Namespaces

- namespace [L4Re](#)  
*L4Re C++ Interfaces.*

### 16.354.1 Detailed Description

Parent interface.

Definition in file [parent](#).

## 16.355 parent

[Go to the documentation of this file.](#)

```

00001 // -*- Mode: C++ -*-
00002 // vim:ft=cpp
00007 /*
00008  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00009  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00010  *      economic rights: Technische Universität Dresden (Germany)
00011  *
00012  * License: see LICENSE.spdx (in this directory or the directories above)
00013  */
00014 #pragma once
00015
00016 #include <l4/sys/capability>
00017 #include <l4/re/protocols.h>
00018 #include <l4/sys/cxx/ipc_iface>
00019
00020 namespace L4Re {
00021
00034
00042 class L4_EXPORT Parent :
00043     public L4::Kobject_t<Parent, L4::Kobject, L4RE_PROTO_PARENT>
00044 {
00045 public:
00061     L4_INLINE_RPC(l4_ret_t, signal, (unsigned long sig, unsigned long val));
00062     typedef L4::Typeid::Rpc<signal_t> Rpc;
00063 };
00064 };
00065

```

## 16.356 l4/re/parent-sys.h File Reference

Parent protocol definition.

### Namespaces

- namespace [L4Re](#)  
*[L4Re C++ Interfaces.](#)*

### Enumerations

- enum [L4Re::Parent\\_::Opcodes](#)  
*Parent communication-protocol opcodes.*

### 16.356.1 Detailed Description

Parent protocol definition.

Definition in file [parent-sys.h](#).

## 16.357 parent-sys.h

[Go to the documentation of this file.](#)

```


00001
00005 /*
00006  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00007  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00008  *      economic rights: Technische Universität Dresden (Germany)
00009  *
00010  * License: see LICENSE.spdx (in this directory or the directories above)
00011  */
00012 #pragma once
00013
00014 namespace L4Re
00015 {
00016     namespace Parent_
00017     {
00023         enum Opcodes { Signal };
00024     };
00025 };

```

## 16.358 l4/re/protocols.h File Reference

[L4Re](#) Protocol Constants (C version).

This graph shows which files directly or indirectly include this file:



## Enumerations

```
enum L4re_protocols {
    L4RE_PROTO_DATASPACE = 0x4000 , L4RE_PROTO_NAMESPACE , L4RE_PROTO_PARENT ,
    L4RE_PROTO_GOOS ,
    L4RE_PROTO_RSVD_1 , L4RE_PROTO_RM , L4RE_PROTO_EVENT , L4RE_PROTO_INHIBITOR ,
    L4RE_PROTO_DMA_SPACE , L4RE_PROTO_MMIO_SPACE , L4RE_PROTO_ITAS , L4RE_PROTO_MEM_ALLOC
    ,
    L4RE_PROTO_REMOTE_ACCESS , L4RE_PROTO_DEBUG = ~0x7fffL }

```

Common *L4Re* Protocol Constants.

### 16.358.1 Detailed Description

*L4Re* Protocol Constants (C version).

Definition in file [protocols.h](#).

## 16.359 protocols.h

[Go to the documentation of this file.](#)

```
00001
00005
00006 /*
00007  * (c) 2015 Alexander Warg <alexander.warg@kernkonzept.com>
00008  *
00009  * License: see LICENSE.spdx (in this directory or the directories above)
00010  */
00011
00012 #pragma once
00013
00019
00024 enum L4re_protocols
00025 {
00026     L4RE_PROTO_DATASPACE = 0x4000,
00027     L4RE_PROTO_NAMESPACE,
00028     L4RE_PROTO_PARENT,
00029     L4RE_PROTO_GOOS,
00030     L4RE_PROTO_RSVD_1,
00031     L4RE_PROTO_RM,
00032     L4RE_PROTO_EVENT,
00033     L4RE_PROTO_INHIBITOR,
00034     L4RE_PROTO_DMA_SPACE,
00035     L4RE_PROTO_MMIO_SPACE,
00036     L4RE_PROTO_ITAS,
00037     L4RE_PROTO_MEM_ALLOC,
00038     L4RE_PROTO_REMOTE_ACCESS,
00039
00040     L4RE_PROTO_DEBUG = ~0x7fffL
00041 };
00042

```


## 16.360 l4/re/random File Reference

Random number generator interface definition.

```
#include <l4/sys/capability>
#include <l4/sys/cxx/ipc_types>
#include <l4/sys/cxx/ipc_iface>

```

Include dependency graph for random:



- struct `L4Re::Random`  
*Low-bandwidth interface for random number generators.*

- namespace **L4Re**  
*L4Re C++ Interfaces.*

Definition in file [random](#).

## 16.361 random

[Go to the documentation of this file.](#)

```

00001 // -*- Mode: C++ -*-
00002 /*
00003  * Copyright (C) 2019-2020, 2022, 2024 Kernkonzept GmbH.
00004  * Author(s): Sarah Hoffmann <sarah.hoffmann@kernkonzept.com>
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00012 #pragma once
00013
00014 #include <l4/sys/capability>
00015 #include <l4/sys/cxx/ipc_types>
00016 #include <l4/sys/cxx/ipc_iface>
00017 #include <l4/sys/icu>
00018
00019 namespace L4Re
00020 {
00021
00033 struct L4_EXPORT Random
00034 : public L4::Kobject_t<Random, L4::Icu>
00035 {
00060     L4_INLINE_RPC(long, get_random, (l4_size_t size,
00061                                     L4::Ipc::Array<char, unsigned long> *buffer));
00062
00063     typedef L4::Typeid::Rpcs<get_random_t> Rpcs;
00064 };
00065
00066 } // namespace

```

## 16.362 remote\_access

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00002 /*
00003  * Copyright (C) 2025 Adam Lackorzynski <adam@l4re.org>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007
00008 #pragma once
00009
00010 #include <l4/re/protocols.h>
00011 #include <l4/re/dataspace>
00012 #include <l4/sys/cxx/ipc_iface>
00013 #include <l4/sys/cxx/ipc_types>
00014 #include <l4/sys/cxx/types>
00015 #include <l4/sys/l4int.h>
00016
00017 namespace L4Re
00018 {
00019
00020 struct L4_EXPORT Remote_access
00021 : public L4::Kobject_t<Remote_access, Dataspace, L4RE_PROTO_REMOTE_ACCESS>
00022 {
00023     enum Access_width
00024     {
00025         Wd_8bit = 0,
00026         Wd_16bit = 1,
00027         Wd_32bit = 2,
00028         Wd_64bit = 3
00029     };
00030
00031     L4_INLINE_RPC(long, read_mem, (l4_addr_t addr, char width, l4_uint64_t *value));
00032     L4_INLINE_RPC(long, write_mem, (l4_addr_t addr, char width, l4_uint64_t value));
00033
00034     //L4_INLINE_RPC(long, get_regs, (unsigned TBD_THREAD_ID, l4_exc_regs_t *regs));
00035     //L4_INLINE_RPC(long, set_regs, (unsigned TBD_THREAD_ID, l4_exc_regs_t regs));
00036
00037     // !!! sizeof(l4_fpu_regs_t) > sizeof(utcb)
00038     //L4_INLINE_RPC(long, get_fpu_regs, (l4_fpu_regs_t *regs));
00039     //L4_INLINE_RPC(long, set_fpu_regs, (l4_fpu_regs_t regs));
00040
00041     L4_INLINE_RPC(long, terminate, (int exit_code), L4::Ipc::Send_only);
00042
00043     typedef L4::Typeid::Rpcs<read_mem_t, write_mem_t, terminate_t> Rpcs;
00044 };
00045
00046 }

```




## 16.363 l4/re/rm File Reference


Region mapper interface.

```
#include <l4/sys/types.h>
#include <l4/sys/l4int.h>
#include <l4/sys/capability>
#include <l4/re/protocols.h>
#include <l4/sys/pager>
#include <l4/sys/cxx/ipc_iface>
#include <l4/sys/cxx/ipc_ret_array>
#include <l4/sys/cxx/types>
#include <l4/re/consts>
#include <l4/re/dataspace>
```

Include dependency graph for rm:



This graph shows which files directly or indirectly include this file:



### Data Structures

- class `L4Re::Rm`  
*Region map.*
- struct `L4Re::Rm::F`  
*Rm flags definitions.*
- class `L4Re::Rm::Unique_region< T >`  
*Unique region.*
- struct `L4Re::Rm::Region`  
*A region is a range of virtual addresses which is backed by content.*
- struct `L4Re::Rm::Area`  
*An area is a range of virtual addresses which is reserved, see `L4Re::Rm::reserve_area()`.*

## Namespaces

- namespace [L4Re](#)  
*[L4Re](#) C++ Interfaces.*

### 16.363.1 Detailed Description

Region mapper interface.

Definition in file [rm](#).

## 16.364 rm

[Go to the documentation of this file.](#)

```

00001 // -*- Mode: C++ -*-
00002 // vim:ft=cpp
00007 /*
00008  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00009  *      Alexander Warg <warg@os.inf.tu-dresden.de>,
00010  *      Björn Döbel <doebel@os.inf.tu-dresden.de>,
00011  *      Torsten Frenzel <frenzel@os.inf.tu-dresden.de>
00012  *      economic rights: Technische Universität Dresden (Germany)
00013  *
00014  * License: see LICENSE.spdx (in this directory or the directories above)
00015  */
00016 #pragma once
00017
00018 #include <l4/sys/types.h>
00019 #include <l4/sys/l4int.h>
00020 #include <l4/sys/capability>
00021 #include <l4/re/protocols.h>
00022 #include <l4/sys/pager>
00023 #include <l4/sys/cxx/ipc_iface>
00024 #include <l4/sys/cxx/ipc_ret_array>
00025 #include <l4/sys/cxx/types>
00026 #include <l4/re/consts>
00027 #include <l4/re/dataspace>
00028
00029 namespace L4Re {
00030
00073
00081 class L4_EXPORT Rm :
00082     public L4::Kobject_t<Rm, L4::Pager, L4RE_PROTO_RM,
00083         L4::Type_info::Demand_t<1> >
00084 {
00085 public:
00086     typedef L4Re::Dataspace::Offset Offset;
00087
00089     enum Detach_result
00090     {
00091         Detached_ds    = 0,
00092         Kept_ds        = 1,
00093         Split_ds       = 2,
00094         Detach_result_mask = 3,
00095
00096         Detach_again = 4,
00097     };
00098
00100     enum Region_flag_shifts
00101     {
00103         Caching_shift    = Dataspace::F::Caching_shift,
00104     };
00105
00107     struct F
00108     {
00110         enum Attach_flags : l4_uint32_t
00111         {
00113             Search_addr    = 0x20000,
00115             In_area        = 0x40000,
00117             Eager_map      = 0x80000,
00119             No_eager_map   = 0x100000,
00120
00122             Attach_mask    = 0x1f0000,

```

```

00123     };
00124
00125     friend void enum_bitops_enable(Attach_flags);
00126
00127     enum Region_flags : l4_uint16_t
00128     {
00129     {
00131         Rights_mask = 0x0f,
00133         R           = Dataspace::F::R,
00135         W           = Dataspace::F::W,
00137         X           = Dataspace::F::X,
00139         RW          = Dataspace::F::RW,
00141         RX          = Dataspace::F::RX,
00143         RWX         = Dataspace::F::RWX,
00144
00146         Kernel      = 0x100,
00148         Detach_free  = 0x200,
00150         Pager       = 0x400,
00152         Reserved    = 0x800,
00153
00154
00156         Caching_mask = Dataspace::F::Caching_mask,
00159         Cache_normal = Dataspace::F::Normal,
00161         Cache_buffered = Dataspace::F::Bufferable,
00163         Cache_uncached = Dataspace::F::Uncacheable,
00164
00166         Ds_map_mask  = 0xff,
00167
00169         Region_flags_mask = 0xffff,
00170     };
00171
00172     friend void enum_bitops_enable(Region_flags);
00173
00174     friend constexpr Dataspace::Flags map_flags(Region_flags rf)
00175     { return Dataspace::Flags(static_cast<l4_uint16_t>(rf) & Ds_map_mask); }
00176
00177     struct Flags : L4::Types::Flags_ops_t<Flags>
00178     {
00179         l4_uint32_t raw;
00180
00181         Flags() = default;
00182         explicit constexpr Flags(l4_uint32_t f) : raw(f) {}
00183         constexpr Flags(Attach_flags af) : raw(static_cast<l4_uint32_t>(af)) {}
00184         constexpr Flags(Region_flags rf) : raw(static_cast<l4_uint32_t>(rf)) {}
00185
00186         constexpr Dataspace::Flags map_flags() const
00187         { return Dataspace::Flags(raw & Ds_map_mask); }
00188
00189         constexpr Region_flags region_flags() const
00190         { return Region_flags(raw & Region_flags_mask); }
00191
00192         constexpr Attach_flags attach_flags() const
00193         { return Attach_flags(raw & Attach_mask); }
00194
00195         constexpr bool r() const { return raw & L4_FPAGE_RO; }
00196         constexpr bool w() const { return raw & L4_FPAGE_W; }
00197         constexpr bool x() const { return raw & L4_FPAGE_X; }
00198
00199         constexpr unsigned cap_rights() const
00200         { return w() ? L4_CAP_FPAGE_RW : L4_CAP_FPAGE_RO; }
00201     };
00202
00203     friend constexpr Flags operator | (Region_flags l, Attach_flags r)
00204     { return Flags(l) | Flags(r); }
00205
00206     friend constexpr Flags operator | (Attach_flags l, Region_flags r)
00207     { return Flags(l) | Flags(r); }
00208 };
00209
00210 using Attach_flags = F::Attach_flags;
00211 using Region_flags = F::Region_flags;
00212 using Flags = F::Flags;
00213
00215     enum Detach_flags
00216     {
00226         Detach_exact    = 1,
00227
00237         Detach_overlap  = 2,
00238
00246         Detach_keep     = 4,
00247     };
00248
00276     l4_ret_t reserve_area(l4_addr_t *start, unsigned long size,
00277                          Flags flags = Flags(0),
00278                          unsigned char align = L4_PAGESHIFT) const noexcept
00279     { return reserve_area_t::call(c(), start, size, flags, align); }
00280
00281     L4_RPC_NF(l4_ret_t, reserve_area, (L4::Ipc::In_out<l4_addr_t *> start,

```

```

00282             unsigned long size,
00283             Flags flags,
00284             unsigned char align));
00285
00303     template<typename T>
00304     l4_ret_t reserve_area(T **start, unsigned long size,
00305                          Flags flags = Flags(0),
00306                          unsigned char align = L4_PAGESHIFT) const noexcept
00307     {
00308         return reserve_area_t::call(c(), reinterpret_cast<l4_addr_t*>(start), size,
00309                                     flags, align);
00310     }
00311
00325     L4_RPC(l4_ret_t, free_area, (l4_addr_t addr));
00326
00327     L4_RPC_NF(l4_ret_t, attach, (L4::Ipc::In_out<l4_addr_t *> start,
00328                                unsigned long size, Flags flags,
00329                                L4::Ipc::Opt<L4::Ipc::Cap<Dataspace>> mem,
00330                                Offset offs, unsigned char align,
00331                                L4::Ipc::Opt<l4_cap_idx_t> client_cap,
00332                                L4::Ipc::String<> name, Offset backing_offset));
00333
00334     L4_RPC_NF(l4_ret_t, detach, (l4_addr_t addr, unsigned long size, unsigned flags,
00335                                 l4_addr_t &start, l4_addr_t &rsz,
00336                                 l4_cap_idx_t &mem_cap));
00337
00396     l4_ret_t attach(l4_addr_t *start, unsigned long size, Flags flags,
00397                   L4::Ipc::Cap<Dataspace> mem, Offset offs = 0,
00398                   unsigned char align = L4_PAGESHIFT,
00399                   L4::Cap<L4::Task> const task
00400                   = L4::Cap<L4::Task>::Invalid,
00401                   char const *name = nullptr,
00402                   Offset backing_offset = 0) const noexcept;
00403
00407     template<typename T>
00408     l4_ret_t attach(T **start, unsigned long size, Flags flags,
00409                   L4::Ipc::Cap<Dataspace> mem, Offset offs = 0,
00410                   unsigned char align = L4_PAGESHIFT,
00411                   L4::Cap<L4::Task> const task
00412                   = L4::Cap<L4::Task>::Invalid,
00413                   char const *name = nullptr,
00414                   Offset backing_offset = 0) const noexcept
00415     {
00416         union X { l4_addr_t a; T* t; };
00417         X *x = reinterpret_cast<X*>(start);
00418         return attach(&x->a, size, flags, mem, offs, align, task,
00419                     name, backing_offset);
00420     }
00421
00422     #if __cplusplus >= 201103L
00433     template<typename T>
00434     class Unique_region
00435     {
00436     private:
00437         T _addr;
00438         L4::Cap<Rm> _rm;
00439
00440     public:
00441         Unique_region(Unique_region const &) = delete;
00442         Unique_region &operator = (Unique_region const &) = delete;
00443
00444         Unique_region() noexcept
00445             : _addr(0), _rm(L4::Cap<Rm>::Invalid) {}
00446
00447         explicit Unique_region(T addr) noexcept
00448             : _addr(addr), _rm(L4::Cap<Rm>::Invalid) {}
00449
00455         Unique_region(T addr, L4::Cap<Rm> const &rm) noexcept
00456             : _addr(addr), _rm(rm) {}
00457
00464         Unique_region(Unique_region &&o) noexcept : _addr(o.get()), _rm(o._rm)
00465             { o.release(); }
00466
00472         Unique_region &operator = (Unique_region &&o) noexcept
00473             { o.release(); }
00474
00480         Unique_region &operator = (Unique_region &&o) noexcept
00481             {
00482                 if (&o != this)
00483                 {
00484                     if (_rm.is_valid())
00485                         _rm->detach(reinterpret_cast<l4_addr_t>(_addr), 0);
00486                     _rm = o._rm;
00487                     _addr = o.release();
00488                 }
00489                 return *this;
00490             }
00491
00497         ~Unique_region() noexcept
00498         {

```

```

00499         if (_rm.is_valid())
00500             _rm->detach(reinterpret_cast<l4_addr_t>(_addr), 0);
00501     }
00502
00508     T get() const noexcept
00509     { return _addr; }
00510
00516     T release() noexcept
00517     {
00518         _rm = L4::Cap<Rm>::Invalid;
00519         return _addr;
00520     }
00521
00528     void reset(T addr, L4::Cap<Rm> const &rm) noexcept
00529     {
00530         if (_rm.is_valid())
00531             _rm->detach(l4_addr_t(_addr), 0);
00532
00533         _rm = rm;
00534         _addr = addr;
00535     }
00536
00540     void reset() noexcept
00541     { reset(0, L4::Cap<Rm>::Invalid); }
00542
00548     bool is_valid() const noexcept
00549     { return _rm.is_valid(); }
00550
00552     T operator * () const noexcept { return _addr; }
00553
00555     T operator -> () const noexcept { return _addr; }
00556 };
00557
00558 template<typename T>
00559 l4_ret_t attach(Unique_region<T> *start, unsigned long size, Flags flags,
00560                L4::Ipc::Cap<Dataspace> mem, Offset offs = 0,
00561                unsigned char align = L4_PAGESHIFT,
00562                L4::Cap<L4::Task> const task
00563                = L4::Cap<L4::Task>::Invalid,
00564                char const *name = nullptr,
00565                Offset backing_offset = 0) const noexcept
00566 {
00567     l4_addr_t addr = reinterpret_cast<l4_addr_t>(start->get());
00568
00569     long res = attach(&addr, size, flags, mem, offs, align, task,
00570                     name, backing_offset);
00571     if (res < 0)
00572         return res;
00573
00574     start->reset(reinterpret_cast<T>(&addr), L4::Cap<Rm>(cap()));
00575     return res;
00576 }
00577 #endif
00578
00596     l4_ret_t detach(l4_addr_t addr, L4::Cap<Dataspace> *mem,
00597                   L4::Cap<L4::Task> const &task = This_task) const noexcept;
00598
00602     l4_ret_t detach(void *addr, L4::Cap<Dataspace> *mem,
00603                   L4::Cap<L4::Task> const &task = This_task) const noexcept;
00604
00624     l4_ret_t detach(l4_addr_t start, unsigned long size, L4::Cap<Dataspace> *mem,
00625                   L4::Cap<L4::Task> const &task) const noexcept;
00626
00671     l4_ret_t find(l4_addr_t *addr, unsigned long *size, Offset *offset,
00672                 L4Re::Rm::Flags *flags, L4::Cap<Dataspace> *m) noexcept
00673     { return find_t::call(c(), addr, size, flags, offset, m); }
00674
00675     L4_RPC_NF(l4_ret_t, find, (L4::Ipc::In_out<l4_addr_t *> addr,
00676                             L4::Ipc::In_out<unsigned long *> size,
00677                             L4Re::Rm::Flags *flags, Offset *offset,
00678                             L4::Ipc::As_value<L4::Cap<Dataspace>> *m));
00679
00685     struct Region
00686     {
00687         l4_addr_t start;
00688         l4_addr_t end;
00689         F::Region_flags flags;
00690     };
00691
00698     struct Area
00699     {
00700         l4_addr_t start;
00701         l4_addr_t end;
00702     };
00703
00718     L4_RPC(l4_ret_t, get_regions, (l4_addr_t start, L4::Ipc::Ret_array<Region> regions));
00719

```

```

00734 L4_RPC(long, get_areas, (l4_addr_t start, L4::Ipc::Ret_array<Area> areas));
00735
00749 L4_RPC(l4_ret_t, get_info, (l4_addr_t addr, L4::Ipc::String<char> &name,
00750                               Offset &backing_offset));
00751
00752 l4_ret_t detach(l4_addr_t start, unsigned long size, L4::Cap<Dataspace> *mem,
00753                 L4::Cap<L4::Task> task, unsigned flags) const noexcept;
00754
00755 typedef L4::Typeid::Rpc<attach_t, detach_t, find_t,
00756                        reserve_area_t, free_area_t,
00757                        get_regions_t, get_areas_t,
00758                        get_info_t> Rpc<
00759 >;
00760
00761 inline l4_ret_t
00762 Rm::detach(l4_addr_t addr, L4::Cap<Dataspace> *mem,
00763            L4::Cap<L4::Task> const &task) const noexcept
00764 { return detach(addr, 1, mem, task, Detach_overlap); }
00765
00766 inline l4_ret_t
00767 Rm::detach(void *addr, L4::Cap<Dataspace> *mem,
00768            L4::Cap<L4::Task> const &task) const noexcept
00769 {
00770     return detach(reinterpret_cast<l4_addr_t>(addr), 1, mem, task,
00771                  Detach_overlap);
00772 }
00773
00774 inline l4_ret_t
00775 Rm::detach(l4_addr_t addr, unsigned long size, L4::Cap<Dataspace> *mem,
00776            L4::Cap<L4::Task> const &task) const noexcept
00777 { return detach(addr, size, mem, task, Detach_exact); }
00778
00779 };

```

## 16.365 I4/re/rm-sys.h File Reference

Region mapper protocol definitions.

### Namespaces

- namespace [L4Re](#)  
*L4Re C++ Interfaces.*

### Enumerations

- enum [L4Re::Rm\\_::Opcodes](#)  
*Region-map communication-protocol opcodes.*

### 16.365.1 Detailed Description

Region mapper protocol definitions.

Definition in file [rm-sys.h](#).



## Namespaces

- namespace [L4Re](#)  
*[L4Re](#) C++ Interfaces.*
- namespace [L4Re::Util](#)  
*Documentation of the [L4](#) Runtime Environment utility functionality in C++.*

### 16.367.1 Detailed Description

Bitmap capability allocator.

Definition in file [bitmap\\_cap\\_alloc](#).

## 16.368 bitmap\_cap\_alloc

[Go to the documentation of this file.](#)

```

00001 // -*- Mode: C++ -*-
00002 // vim:ft=cpp
00007 /*
00008  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00009  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00010  *      economic rights: Technische Universität Dresden (Germany)
00011  *
00012  * License: see LICENSE.spdx (in this directory or the directories above)
00013  */
00014
00015 #pragma once
00016
00017 #include <l4/re/util/item_alloc>
00018 #include <l4/sys/assert.h>
00019 #include <l4/sys/capability>
00020 #include <l4/sys/task.h>
00021
00022 namespace L4Re { namespace Util {
00023
00028 class Cap_alloc_base
00029 {
00030 private:
00031     long _bias;
00032     Item_alloc_base _items;
00033
00034 public:
00035     template <unsigned COUNT>
00036     struct Storage
00037     {
00038         typename Bitmap_base::Word<COUNT>::Type _bits[Bitmap_base::Word<COUNT>::Size];
00039     };
00040
00041     enum State { Free = 0, Allocated, Unknown };
00042     Cap_alloc_base(long max, void *mem, long bias = 0, void * = 0)
00043         noexcept : _bias(bias), _items(max, mem) {}
00044
00045     L4::Cap<void> alloc() noexcept
00046     {
00047         long cap = _items.alloc();
00048         if (cap < 0)
00049             return L4::Cap<void>::Invalid;
00050
00051         return L4::Cap<void>((cap + _bias) « L4_CAP_SHIFT);
00052     }
00053
00054     long hint() const { return _items.hint(); }
00055
00059     template< typename T >
00060     L4::Cap<T> alloc() noexcept
00061     { return L4::Cap<T>(alloc().cap()); }
00062
00063     State is_allocated(L4::Cap<void> c) const noexcept
00064     {
00065         long idx = (c.cap() » L4_CAP_SHIFT);
00066
00067         if (idx < _bias)

```



```

00068         return Unknown;
00069
00070         idx -= _bias;
00071         if (idx >= _items.size())
00072             return Unknown;
00073
00074         return _items.is_allocated(idx) ? Allocated : Free;
00075     }
00076
00077     template< typename T>
00081     void free(L4::Cap<T> const &cap, l4_cap_idx_t task = L4_INVALID_CAP,
00082              l4_umword_t unmap_flags = L4_FP_ALL_SPACES) noexcept
00083     {
00084         long idx = (cap.cap() >> L4_CAP_SHIFT);
00085         if (idx < _bias)
00086             return;
00087
00088         idx -= _bias;
00089         if (idx >= _items.size())
00090             return;
00091
00092         l4_assert(_items.is_allocated(idx));
00093
00094         if (l4_is_valid_cap(task))
00095             l4_task_unmap(task, cap.fpage(), unmap_flags | 2);
00096
00097         _items.free(idx);
00098     }
00099
00100     // since we have no counters assume counter always > 0
00101     void take(L4::Cap<void>) noexcept {}
00102     bool release(L4::Cap<void>, l4_cap_idx_t /*task*/ = L4_INVALID_CAP,
00103                 unsigned /*unmap_flags*/ = L4_FP_ALL_SPACES) noexcept
00104     { return false; }
00105
00106     long last() noexcept
00107     {
00108         return _items.size() + _bias - 1;
00109     }
00110 };
00111
00112 template< long Size >
00113 class Cap_alloc : public Cap_alloc_base
00114 {
00115 private:
00116     typename Bitmap_base::Word<Size>::Type _bits[Bitmap_base::Word<Size>::Size];
00117
00118 public:
00119     explicit Cap_alloc(long bias = 0) noexcept
00120         : Cap_alloc_base(Size, _bits, bias) {}
00121
00122 };
00123
00124 }
00125 }

```

## 16.369 br\_manager

```

00001 // vi:set ft=c++: -- Mode: C++ --
00002 /*
00003  * (c) 2014 Alexander Warg <alexander.warg@kernkonzept.com>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007
00008 #pragma once
00009
00010 #include <l4/re/util/cap_alloc>
00011 #include <l4/sys/cxx/ipc_server_loop>
00012 #include <l4/cxx/ipc_timeout_queue>
00013 #include <l4/sys/assert.h>
00014
00015 namespace L4Re { namespace Util {
00016
00025     class Br_manager : public L4::Ipc_svr::Server_iface
00026     {
00027     private:
00028         enum { _mem = 0, _ports = 0 };
00029         enum { Brs_per_timeout = sizeof(l4_kernel_clock_t) / sizeof(l4_umword_t) };
00030
00031     public:
00033         Br_manager() : _caps(0), _cap_flags(L4_RCV_ITEM_LOCAL_ID) {}
00034

```

```

00035 Br_manager(Br_manager const &) = delete;
00036 Br_manager &operator = (Br_manager const &) = delete;
00037
00038 Br_manager(Br_manager &&) = delete;
00039 Br_manager &operator = (Br_manager &&) = delete;
00040
00041 ~Br_manager()
00042 {
00043     // Slots for received capabilities are placed at the beginning of the
00044     // (shadowed) buffer registers. Free those.
00045     for (unsigned i = 0; i < _caps; ++i)
00046         cap_alloc.free(L4::Cap<void>(_brs[i] & L4_CAP_MASK));
00047 }
00048
00049 /*
00050  * This implementation dynamically manages assignment of buffer registers for
00051  * the necessary amount of receive buffers allocated by all calls to this
00052  * function.
00053  */
00054 int alloc_buffer_demand(Demand const &d) override
00055 {
00056     using L4::Ipc::Small_buf;
00057
00058     // memory and IO port receive windows currently not supported
00059     if (d.mem || d.ports)
00060         return -L4_EINVAL;
00061
00062     // take extra buffers for a possible timeout and for a zero terminator
00063     if (d.caps + d.mem * 2 + d.ports * 2 + Brs_per_timeout + 1
00064         > L4_UTCB_GENERIC_BUFFERS_SIZE)
00065         return -L4_ERANGE;
00066
00067     if (d.caps > _caps)
00068     {
00069         while (_caps < d.caps)
00070         {
00071             L4::Cap<void> cap = cap_alloc.alloc();
00072             if (!cap)
00073                 return -L4_ENOMEM;
00074
00075             reinterpret_cast<Small_buf&>(_brs[_caps])
00076                 = Small_buf(cap.cap(), _cap_flags);
00077             ++_caps;
00078         }
00079         _brs[_caps] = 0;
00080     }
00081
00082     return L4_EOK;
00083 }
00084
00085
00086 L4::Cap<void> get_rcv_cap(int i) const override
00087 {
00088     if (i < 0 || i >= _caps)
00089         return L4::Cap<void>::Invalid;
00090
00091     return L4::Cap<void>(_brs[i] & L4_CAP_MASK);
00092 }
00093
00094 int realloc_rcv_cap(int i) override
00095 {
00096     using L4::Ipc::Small_buf;
00097
00098     if (i < 0 || i >= _caps)
00099         return -L4_EINVAL;
00100
00101     L4::Cap<void> cap = cap_alloc.alloc();
00102     if (!cap)
00103         return -L4_ENOMEM;
00104
00105     reinterpret_cast<Small_buf&>(_brs[i])
00106         = Small_buf(cap.cap(), _cap_flags);
00107
00108     return L4_EOK;
00109 }
00110
00111 void set_rcv_cap_flags(unsigned long flags)
00112 {
00113     l4_assert(_caps == 0);
00114
00115     _cap_flags = flags;
00116 }
00117
00118 int add_timeout(L4::Ipc_svr::Timeout *, l4_kernel_clock_t) override
00119 { return -L4_ENOSYS; }
00120
00121 int remove_timeout(L4::Ipc_svr::Timeout *) override

```

```

00131     { return -L4_ENOSYS; }
00132
00134 void setup_wait(l4_utcb_t *utcb, L4::Ipc_svr::Reply_mode)
00135 {
00136     l4_buf_regs_t *br = l4_utcb_br_u(utcb);
00137     br->bdr = 0;
00138     for (unsigned i = 0; i <= _caps; ++i)
00139         br->br[i] = _brs[i];
00140 }
00141
00142 protected:
00144 unsigned first_free_br() const
00145 {
00146     // The last BR (64-bit) or the last two BRs (32-bit); this is constant.
00147     return L4_UTCB_GENERIC_BUFFERS_SIZE - Brs_per_timeout;
00148     // We could also do the following dynamic approach:
00149     // return _caps + _mem + _ports + 1
00150 }
00151
00152 private:
00153     unsigned short _caps;
00154     unsigned long _cap_flags;
00155
00156     l4_umword_t _brs[L4_UTCB_GENERIC_BUFFERS_SIZE];
00157 };
00158
00165 struct Br_manager_hooks
00166 : L4::Ipc_svr::Ignore_errors,
00167   L4::Ipc_svr::Default_timeout,
00168   L4::Ipc_svr::Compound_reply,
00169   Br_manager
00170 {};
00171
00179 struct Br_manager_timeout_hooks :
00180     public L4::Ipc_svr::Timeout_queue_hooks<Br_manager_timeout_hooks, Br_manager>,
00181     public L4::Ipc_svr::Ignore_errors
00182 {
00183     public:
00184         static l4_kernel_clock_t now()
00185         { return l4_kip_clock(l4re_kip()); }
00186 };
00187
00188 {}
00189

```

## 16.370 I4/re/util/cap File Reference

Capability utility functions.




```
00011      * License: see LICENSE.spdx (in this directory or the directories above)
00012      */
00013
00014 #pragma once
00015
00016 #include <l4/sys/task>
00017
00018 namespace L4Re { namespace Util {
00019
00020     L4_CV static inline l4_msgtag_t cap_release(L4::Cap<void> cap)
00021     {
00022         return l4_task_unmap(L4_BASE_TASK_CAP,
00023                             l4_obj_fpage(cap.cap(), 0, L4_FPAGE_RWX),
00024                             L4_FP_ALL_SPACES);
00025     }
00026 }
00027 }
```

### 16.372 I4/re/cap\_alloc File Reference


## Abstract capability-allocator interface.

```
#include <l4/sys/task>
#include <l4/sys/smart_capability>
#include <l4/re/consts>
#include <l4/cxx/type_traits>
```

Include dependency graph for cap\_alloc:



This graph shows which files directly or indirectly include this file:



## Data Structures

- class [L4Re::Cap\\_alloc](#)  
*Capability allocator interface.*
- class [L4Re::Smart\\_cap\\_auto< Unmap\\_flags >](#)  
*Helper for [Unique\\_cap](#) and [Unique\\_del\\_cap](#).*
- class [L4Re::Smart\\_count\\_cap< Unmap\\_flags >](#)  
*Helper for [Ref\\_cap](#) and [Ref\\_del\\_cap](#).*

## Namespaces

- namespace [L4Re](#)  
*[L4Re](#) C++ Interfaces.*

## 16.372.1 Detailed Description

Abstract capability-allocator interface.

Definition in file [cap\\_alloc](#).

## 16.373 cap\_alloc

[Go to the documentation of this file.](#)

```

00001 // vi:set ft=c++: -- Mode: C++ --
00002 /*
00003  * (c) 2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00004  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00005  *      economic rights: Technische Universität Dresden (Germany)
00006  *
00007  * License: see LICENSE.spdx (in this directory or the directories above)
00008  */
00009 #pragma once
00010 #include <l4/sys/task>
00011 #include <l4/sys/smart_capability>
00012 #include <l4/re/consts>
00013 #include <l4/cxx/type_traits>
00014

```

```


00021 namespace L4Re {
00022
00030 class Cap_alloc
00031 {
00032 public:
00033     constexpr Cap_alloc() = default;
00034
00035     // Attention: do *not* define a destructor. We must keep the class trivially
00036     // destructible so that no global destructor is created for
00037     // L4Re::Util::cap_alloc.
00038     // virtual ~Cap_alloc() = default;
00039
00040     Cap_alloc(Cap_alloc const &) = delete;
00041     Cap_alloc &operator = (Cap_alloc const &) = delete;
00042
00047     virtual L4::Cap<void> alloc() noexcept = 0;
00048     virtual void take(L4::Cap<void> cap) noexcept = 0;
00049
00054     template< typename T >
00055     L4::Cap<T> alloc() noexcept
00056     { return L4::cap_cast<T>(alloc()); }
00057
00064     virtual void free(L4::Cap<void> cap, l4_cap_idx_t task = L4_INVALID_CAP,
00065                     unsigned unmap_flags = L4_FP_ALL_SPACES) noexcept = 0;
00066     virtual bool release(L4::Cap<void> cap, l4_cap_idx_t task = L4_INVALID_CAP,
00067                        unsigned unmap_flags = L4_FP_ALL_SPACES) noexcept = 0;
00068 };
00069
00070 template<typename ALLOC>
00071 struct Cap_alloc_t : ALLOC, L4Re::Cap_alloc
00072 {
00073     template<typename ...ARGS>
00074     Cap_alloc_t(ARGS &&...args) : ALLOC(cxx::forward<ARGS>(args)...) {}
00075
00076     L4::Cap<void> alloc() noexcept override { return ALLOC::alloc(); }
00077     void take(L4::Cap<void> cap) noexcept override { ALLOC::take(cap); }
00078
00079     template <typename T>
00080     L4::Cap<T> alloc() noexcept
00081     {
00082         return L4::cap_cast<T>(alloc());
00083     }
00084
00085     void free(L4::Cap<void> cap, l4_cap_idx_t task = L4_INVALID_CAP,
00086             unsigned unmap_flags = L4_FP_ALL_SPACES) noexcept override
00087     { ALLOC::free(cap, task, unmap_flags); }
00088
00089     bool release(L4::Cap<void> cap, l4_cap_idx_t task,
00090                unsigned unmap_flags) noexcept override
00091     { return ALLOC::release(cap, task, unmap_flags); }
00092
00093     void operator delete(void *) {}
00094 };
00095
00096 extern Cap_alloc *virt_cap_alloc;
00097
00102 template< unsigned long Unmap_flags = L4_FP_ALL_SPACES >
00103 class Smart_cap_auto
00104 {
00105 private:
00106     Cap_alloc *_ca;
00107
00108 public:
00109     Smart_cap_auto() : _ca(0) {}
00110     Smart_cap_auto(Cap_alloc *ca) : _ca(ca) {}
00111
00112     void free(L4::Cap_base &c)
00113     {
00114         if (c.is_valid() && _ca)
00115             _ca->free(L4::Cap<void>(c.cap()), This_task, Unmap_flags);
00116
00117         invalidate(c);
00118     }
00119
00120     static void invalidate(L4::Cap_base &c)
00121     {
00122         if (c.is_valid())
00123             c.invalidate();
00124     }
00125
00126 };
00127
00131 template< unsigned long Unmap_flags = L4_FP_ALL_SPACES >
00132 class Smart_count_cap
00133 {
00134 private:
00135     Cap_alloc *_ca;

```





This graph shows which files directly or indirectly include this file:



## Data Structures

- class [L4Re::Util::Smart\\_cap\\_auto< Unmap\\_flags >](#)  
Helper for *Unique\_cap* and *Unique\_del\_cap*.
- class [L4Re::Util::Smart\\_count\\_cap< Unmap\\_flags >](#)  
Helper for *Ref\_cap* and *Ref\_del\_cap*.
- struct [L4Re::Util::Ref\\_cap< T >](#)  
Automatic capability that implements automatic free and unmap of the capability selector.
- struct [L4Re::Util::Ref\\_del\\_cap< T >](#)  
Automatic capability that implements automatic free and unmap+delete of the capability selector.

## Namespaces

- namespace [L4Re](#)  
*L4Re C++ Interfaces.*
- namespace [L4Re::Util](#)  
Documentation of the *L4 Runtime Environment* utility functionality in C++.

## Functions

- template<typename T>  
[Ref\\_cap< T >::Cap L4Re::Util::make\\_ref\\_cap \(\)](#)  
Allocate a capability slot and wrap it in a *Ref\_cap*.
- template<typename T>  
[Ref\\_del\\_cap< T >::Cap L4Re::Util::make\\_ref\\_del\\_cap \(\)](#)  
Allocate a capability slot and wrap it in a *Ref\_del\_cap*.

## Variables

- [\\_Cap\\_alloc L4Re::Util::cap\\_alloc](#)  
Capability allocator.

## 16.374.1 Detailed Description

Capability allocator.

Definition in file [cap\\_alloc](#).

## 16.375 cap\_alloc

[Go to the documentation of this file.](#)


```

00001 // -*- Mode: C++ -*-
00002 // vim:ft=cpp
00003 /*
00004  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00005  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00006  *      economic rights: Technische Universität Dresden (Germany)
00007  *
00008  * License: see LICENSE.spdx (in this directory or the directories above)
00009  */
00010
00011 #pragma once
00012
00013 #include <l4/re/util/cap_alloc_impl.h>
00014 #include <l4/sys/smart_capability>
00015 #include <l4/sys/task>
00016 #include <l4/re/consts>
00017
00018 namespace L4Re { namespace Util {
00019
00020 extern _Cap_alloc cap_alloc;
00021
00022 template< unsigned long Unmap_flags = L4_FP_ALL_SPACES >
00023 class Smart_cap_auto
00024 {
00025 public:
00026     static void free(L4::Cap_base &c)
00027     {
00028         if (c.is_valid())
00029         {
00030             cap_alloc.free(L4::Cap<void>(c.cap()), This_task, Unmap_flags);
00031             c.invalidate();
00032         }
00033     }
00034
00035     static void invalidate(L4::Cap_base &c)
00036     {
00037         if (c.is_valid())
00038             c.invalidate();
00039     }
00040 };
00041
00042 template< unsigned long Unmap_flags = L4_FP_ALL_SPACES >
00043 class Smart_count_cap
00044 {
00045 public:
00046     static void free(L4::Cap_base &c) noexcept
00047     {
00048         if (c.is_valid())
00049         {
00050             if (cap_alloc.release(L4::Cap<void>(c.cap()), This_task, Unmap_flags))
00051                 c.invalidate();
00052         }
00053     }
00054
00055     static void invalidate(L4::Cap_base &c) noexcept
00056     {
00057         if (c.is_valid())
00058             c.invalidate();
00059     }
00060
00061     static L4::Cap_base copy(L4::Cap_base const &src)
00062     {
00063         cap_alloc.take(L4::Cap<void>(src.cap()));
00064         return src;
00065     }
00066 };


```

## 16.376 l4/re/util/cap\_alloc\_impl.h File Reference

```
#include <l4/bid_config.h>
#include <l4/re/cap_alloc>
#include <l4/re/util/counting_cap_alloc>
#include <l4/re/util/debug>
Include dependency graph for cap_alloc_impl.h:
```



This graph shows which files directly or indirectly include this file:



## Data Structures

- class [L4Re::Util::\\_Cap\\_alloc](#)

Adapter to expose the cap allocator implementation as [L4Re::Cap\\_alloc](#) compatible class.

## Namespaces

- namespace [L4Re](#)  
[L4Re C++ Interfaces.](#)
- namespace [L4Re::Util](#)

Documentation of the [L4 Runtime Environment](#) utility functionality in C++.

## 16.376.1 Detailed Description

Capability allocator implementation.

Definition in file [cap\\_alloc\\_impl.h](#).

## 16.377 cap\_alloc\_impl.h

[Go to the documentation of this file.](#)

```
00001 // -*- Mode: C++ -*-
00002 // vim:ft=cpp
00003 /*
00004  * (c) 2008-2009 Alexander Warg <warg@os.inf.tu-dresden.de>
00005  *     economic rights: Technische Universität Dresden (Germany)
00006  *
00007  * License: see LICENSE.spdx (in this directory or the directories above)
00008  */
00009 #pragma once
00010
00011 #include <l4/bid_config.h>
00012 #include <l4/re/cap_alloc>
00013
00014 #if defined(CONFIG_L4RE_BITMAP_CAP_ALLOC)
00015 #include <l4/re/util/bitmap_cap_alloc>
00016
00017 namespace L4Re { namespace Util {
```

```

00025 using _Cap_alloc_impl = Cap_alloc_base;
00026
00027 }}
00028
00029 #elif defined(CONFIG_L4RE_COUNTING_CAP_ALLOC)
00030
00031 #include <l4/re/util/counting_cap_alloc>
00032 #include <l4/re/util/debug>
00033
00034 namespace L4Re { namespace Util {
00035
00036 // RISC-V does not natively support subword atomics, such as __atomic_load_1.
00037 // The RISC-V gcc developers have decided to emulate these via libatomic, which
00038 // is automatically linked against.
00039 #if defined(__GCC_HAVE_SYNC_COMPARE_AND_SWAP_1) || defined(ARCH_arm) || defined(ARCH_riscv)
00040 using _Cap_alloc_impl
00041     = Counting_cap_alloc<L4Re::Util::Counter_atomic<unsigned char>,
00042         L4Re::Util::Dbg>;
00043 #elif defined(ARCH_sparc)
00044 using _Cap_alloc_impl
00045     = Counting_cap_alloc<L4Re::Util::Counter<unsigned char>,
00046         L4Re::Util::Dbg>;
00047 #warning "Thread-safe capability allocator not available!"
00048 #else
00049 #error "Unsupported platform"
00050 #endif
00051
00052 }}
00053
00054 #else
00055 #error "No supported capability allocator selected"
00056 #endif
00057
00058 namespace L4Re { namespace Util {
00059
00060 class _Cap_alloc final : public L4Re::Cap_alloc, private _Cap_alloc_impl
00061 {
00062 public:
00063     template <unsigned COUNT>
00064     using Storage = _Cap_alloc_impl::Storage<COUNT>;
00065
00066     using _Cap_alloc_impl::_Cap_alloc_impl; // Expose underlying constructor
00067     void operator delete(void *) {} // Prevent global operator delete reference
00068
00069     L4::Cap<void> alloc() noexcept override
00070     { return _Cap_alloc_impl::alloc(); }
00071
00072     template< typename T >
00073     L4::Cap<T> alloc() noexcept
00074     { return L4::cap_cast<T>(alloc()); }
00075
00076     void take(L4::Cap<void> cap) noexcept override
00077     { _Cap_alloc_impl::take(cap); }
00078
00079     void free(L4::Cap<void> cap, l4_cap_idx_t task = L4_INVALID_CAP,
00080         unsigned unmap_flags = L4_FP_ALL_SPACES) noexcept override
00081     { _Cap_alloc_impl::free(cap, task, unmap_flags); }
00082
00083     bool release(L4::Cap<void> cap, l4_cap_idx_t task,
00084         unsigned unmap_flags) noexcept override
00085     { return _Cap_alloc_impl::release(cap, task, unmap_flags); }
00086
00087     using _Cap_alloc_impl::last;
00088 };
00089
00090 }}

```

## 16.378 l4/re/util/counting\_cap\_alloc File Reference


Reference-counting capability allocator.

```


#include <l4/sys/task>
#include <l4/sys/assert.h>
#include <l4/re/consts>

```

Include dependency graph for counting\_cap\_alloc:



This graph shows which files directly or indirectly include this file:



## Data Structures

- struct `L4Re::Util::Counter< COUNTER >`  
*Counter for `Counting_cap_alloc` with variable data width.*
- struct `L4Re::Util::Counter_atomic< COUNTER >`  
*Thread safe version of counter for `Counting_cap_alloc`.*
- class `L4Re::Util::Counting_cap_alloc< COUNTERTYPE, Dbg >`  
*Internal reference-counting cap allocator.*

## Namespaces

- namespace [L4Re](#)  
[L4Re C++ Interfaces](#).
- namespace [L4Re::Util](#)  
*Documentation of the [L4 Runtime Environment](#) utility functionality in C++.*

## 16.378.1 Detailed Description

Reference-counting capability allocator.

Definition in file [counting\\_cap\\_alloc](#).

## 16.379 counting\_cap\_alloc

[Go to the documentation of this file.](#)

```

00001 // vim:set ft=cpp: -*- Mode: C++ -*-
00006 /*
00007  * (c) 2008-2010 Alexander Warg <warg@os.inf.tu-dresden.de>
00008  *      economic rights: Technische Universität Dresden (Germany)
00009  *
00010  * License: see LICENSE.spdx (in this directory or the directories above)
00011  */
00012
00013 #pragma once
00014
00015 #include <l4/sys/task>
00016 #include <l4/sys/assert.h>
00017 #include <l4/re/consts>
00018
00019 namespace L4Re { namespace Util {
00020
00026 template< typename COUNTER = unsigned char >
00027 struct Counter
00028 {
00029     typedef COUNTER Type;
00030     Type _cnt;
00031
00032     static Type nil() { return 0; }
00033     static Type unused() { return 0; }
00034
00035     void free() { _cnt = 0; }
00036     bool is_free() const { return _cnt == 0; }
00037     bool is_saturated() const { return static_cast<Type>(_cnt + 1) == 0; }
00038
00050     bool inc()
00051     {
00052         if (is_saturated())
00053             return true; // no change and no warning
00054         ++_cnt;
00055         if (is_saturated())
00056             return false; // warn caller that counter is now saturated
00057         else
00058             return true; // success
00059     }
00060
00067     Type dec()
00068     {
00069         if (is_saturated())
00070             return _cnt; // no change
00071         else
00072             return --_cnt; // success
00073     }
00074
00075     bool try_alloc()
00076     {
00077         if (_cnt == 0)
00078         {
00079             _cnt = 1;
00080             return true;
00081         }
00082         return false;
00083     }
00084 };
00085
00097 template< typename COUNTER = unsigned char >
00098 struct Counter_atomic
00099 {
00100     typedef COUNTER Type;
00101     Type _cnt;
00102
00103     static Type nil() { return 0; }
00104     static Type unused() { return 1; }
00105
00106     bool is_free() const { return __atomic_load_n(&_cnt, __ATOMIC_RELAXED) == 0; }

```

```

00107 static bool is_saturated(Type cnt) { return static_cast<Type>(cnt + 1) == 0; }
00108
00109 bool try_alloc()
00110 {
00111     Type expected = nil();
00112     // Use "acquire" memory ordering. Any operations tied to the capability slot
00113     // must only be observable after the slot has been occupied.
00114     return __atomic_compare_exchange_n(&cnt, &expected, 2, false,
00115                                       __ATOMIC_ACQUIRE, __ATOMIC_RELAXED);
00116 }
00117
00121 bool inc()
00122 {
00123     Type old_cnt = __atomic_load_n(&cnt, __ATOMIC_RELAXED);
00124     Type new_cnt;
00125     do
00126     {
00127         if (is_saturated(old_cnt))
00128             return true; // no change and no warning
00129         new_cnt = old_cnt + 1;
00130     }
00131     while (!__atomic_compare_exchange_n(&cnt, &old_cnt, new_cnt, false,
00132                                       __ATOMIC_RELAXED, __ATOMIC_RELAXED));
00133     if (is_saturated(new_cnt))
00134         return false; // warn caller that counter is now saturated
00135     else
00136         return true; // success
00137 }
00138
00142 Type dec()
00143 {
00144     Type old_cnt = __atomic_load_n(&cnt, __ATOMIC_RELAXED);
00145     Type new_cnt;
00146     do
00147     {
00148         if (is_saturated(old_cnt))
00149             return old_cnt; // no change
00150         new_cnt = old_cnt - 1;
00151     }
00152     while (!__atomic_compare_exchange_n(&cnt, &old_cnt, new_cnt, false,
00153                                       __ATOMIC_RELAXED, __ATOMIC_RELAXED));
00154     return new_cnt; // success
00155 }
00156
00157 void free()
00158 {
00159     // Use "release" memory ordering to make sure that any operations tied to
00160     // the capability slot are observable by other threads before the slot can
00161     // be reused.
00162     __atomic_store_n(&cnt, 0, __ATOMIC_RELEASE);
00163 }
00164 };
00165
00190 template <typename COUNTERTYPE, typename Dbg>
00191 class Counting_cap_alloc
00192 {
00193 private:
00194     void operator = (Counting_cap_alloc const &) { }
00195     typedef COUNTERTYPE Counter;
00196
00197     COUNTERTYPE *_items;
00198     long _free_hint;
00199     long _bias;
00200     long _capacity;
00201     Dbg *_dbg;
00202
00203 public:
00204
00205     template <unsigned COUNT>
00206     struct Storage
00207     {
00208         COUNTERTYPE _buf[COUNT];
00209         typedef COUNTERTYPE Buf_type[COUNT];
00210         enum { Size = COUNT };
00211     };
00212
00213     Counting_cap_alloc(long capacity, void *m, long bias, Dbg *dbg) noexcept
00214     : _items((Counter*)m), _free_hint(0), _bias(bias), _capacity(capacity),
00215       _dbg(dbg)
00216     {}
00217
00218 protected:
00224     Counting_cap_alloc() noexcept
00225     : _items(0), _free_hint(0), _bias(0), _capacity(0)
00226     {}
00227
00242     void setup(void *m, long capacity, long bias, Dbg *dbg) noexcept

```



```

00243 {
00244     _items = static_cast<Counter*>(m);
00245     _capacity = capacity;
00246     _bias = bias;
00247     _dbg = dbg;
00248 }
00249
00250 public:
00257 L4::Cap<void> alloc() noexcept
00258 {
00259     long free_hint = __atomic_load_n(&_free_hint, __ATOMIC_RELAXED);
00260
00261     for (long i = free_hint; i < _capacity; ++i)
00262         if (_items[i].try_alloc())
00263         {
00264             _free_hint = i + 1;
00265             return L4::Cap<void>((i + _bias) « L4_CAP_SHIFT);
00266         }
00267
00268     // _free_hint is not necessarily correct in case of multi-threading! Make
00269     // sure we don't miss any potentially free slots.
00270     for (long i = 0; i < free_hint && i < _capacity; ++i)
00271         if (_items[i].try_alloc())
00272         {
00273             _free_hint = i + 1;
00274             return L4::Cap<void>((i + _bias) « L4_CAP_SHIFT);
00275         }
00276
00277     return L4::Cap<void>::Invalid;
00278 }
00279
00281 template <typename T>
00282 L4::Cap<T> alloc() noexcept
00283 {
00284     return L4::cap_cast<T>(alloc());
00285 }
00286
00287 void take(L4::Cap<void> cap) noexcept
00288 {
00289     long c;
00290     if (!range_check_and_get_idx(cap, &c))
00291         return;
00292
00293     if (!L4_UNLIKELY(_items[c].inc()))
00294         _dbg->printf("Warning: Reference counter of cap 0x%x now saturated!\n",
00295             cap.cap() » L4_CAP_SHIFT);
00296 }
00297
00301 bool free(L4::Cap<void> cap, l4_cap_idx_t task = L4_INVALID_CAP,
00302     unsigned unmap_flags = L4_FP_ALL_SPACES) noexcept
00303 {
00304     long c;
00305     if (!range_check_and_get_idx(cap, &c))
00306         return false;
00307
00308     l4_assert(!_items[c].is_free());
00309
00310     if (l4_is_valid_cap(task))
00311         l4_task_unmap(task, cap.fpage(), unmap_flags);
00312
00313     if (c < _free_hint)
00314         _free_hint = c;
00315
00316     _items[c].free();
00317
00318     return true;
00319 }
00320
00321 bool release(L4::Cap<void> cap, l4_cap_idx_t task = L4_INVALID_CAP,
00322     unsigned unmap_flags = L4_FP_ALL_SPACES) noexcept
00323 {
00324     long c;
00325     if (!range_check_and_get_idx(cap, &c))
00326         return false;
00327
00328     l4_assert(!_items[c].is_free());
00329
00330     if (_items[c].dec() == Counter::unused())
00331     {
00332         if (task != L4_INVALID_CAP)
00333             l4_task_unmap(task, cap.fpage(), unmap_flags);
00334
00335         if (c < _free_hint)
00336             _free_hint = c;
00337     }
00338 }
00339
00340
00341
00342
00343
00344
00345
00346
00347
00348
00349
00350
00351
00352
00353
00354
00355
00356
00357
00358
00359
00360
00361
00362
00363
00364
00365
00366
00367
00368
00369
00370
00371
00372
00373
00374
00375

```

```

00376         // Let others allocate this slot only after the l4_task_unmap() has
00377         // finished.
00378         _items[c].free();
00379
00380         return true;
00381     }
00382     return false;
00383 }
00384
00388 long last() noexcept
00389 {
00390     return _capacity + _bias - 1;
00391 }
00392
00393 private:
00394     bool range_check_and_get_idx(L4::Cap<void> cap, long *c)
00395     {
00396         *c = cap.cap() » L4_CAP_SHIFT;
00397         if (*c < _bias)
00398             return false;
00399
00400         *c -= _bias;
00401
00402         return *c < _capacity;
00403     }
00404 };
00405
00406 }}

```

## 16.380 dataspace\_svr

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00002 /*
00003  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00004  *      Alexander Warg <warg@os.inf.tu-dresden.de>,
00005  *      Torsten Frenzel <frenzel@os.inf.tu-dresden.de>
00006  *      economic rights: Technische Universität Dresden (Germany)
00007  *
00008  * License: see LICENSE.spdx (in this directory or the directories above)
00009  */
00010 #pragma once
00011
00012 #include <string.h>
00013 #include <stddef.h>
00014 #include <l4/bid_config.h>
00015 #include <l4/sys/types.h>
00016 #include <l4/cxx/minmax>
00017 #include <l4/re/dataspace>
00018 #include <l4/re/dataspace-sys.h>
00019 #include <l4/sys/cxx/ipc_legacy>
00020
00021 namespace L4Re { namespace Util {
00022
00029 class Dataspace_svr
00030 {
00031 public:
00032     L4_RPC_LEGACY_DISPATCH(L4Re::Dataspace);
00033
00034     typedef L4::Ipc::Snd_fpage::Map_type Map_type;
00035     typedef L4::Ipc::Snd_fpage::Cacheopt Cache_type;
00036
00037     Dataspace_svr() noexcept
00038     : _ds_start(0), _ds_size(0), _map_flags(L4::Ipc::Snd_fpage::Map),
00039       _cache_flags(L4::Ipc::Snd_fpage::Cached)
00040     {}
00041
00042     virtual ~Dataspace_svr() noexcept {}
00043
00057     l4_ret_t map(Dataspace::Offset offset,
00058                 Dataspace::Map_addr local_addr,
00059                 Dataspace::Flags flags,
00060                 Dataspace::Map_addr min_addr,
00061                 Dataspace::Map_addr max_addr,
00062                 L4::Ipc::Snd_fpage &memory)
00063     {
00064         memory = L4::Ipc::Snd_fpage();
00065
00066         offset = l4_trunc_page(offset);
00067         local_addr = l4_trunc_page(local_addr);
00068
00069         if (!check_limit(offset))
00070         {
00071             #if 0

```

```

00072         printf("limit failed: off=%lx sz=%lx\n", offset, size());
00073 #endif
00074         return -L4_ERANGE;
00075     }
00076
00077     min_addr = l4_trunc_page(min_addr);
00078     max_addr = l4_round_page(max_addr);
00079
00080     l4_addr_t addr = _ds_start + offset;
00081     unsigned char order = L4_PAGESHIFT;
00082
00083     while (order < 30 /* limit to 1GB flexpage */)
00084     {
00085         l4_addr_t map_base = l4_trunc_size(addr, order + 1);
00086         if (map_base < _ds_start)
00087             break;
00088
00089         if (map_base + (1UL << (order + 1)) - 1 > (_ds_start + round_size() - 1))
00090             break;
00091
00092         map_base = l4_trunc_size(local_addr, order + 1);
00093         if (map_base < min_addr)
00094             break;
00095
00096         if (map_base + (1UL << (order + 1)) - 1 > max_addr - 1)
00097             break;
00098
00099         l4_addr_t mask = ~(~0UL << (order + 1));
00100         if (local_addr == ~0UL || ((addr ^ local_addr) & mask))
00101             break;
00102
00103         ++order;
00104     }
00105
00106     l4_addr_t map_base = l4_trunc_size(addr, order);
00107
00108     Dataspace::Map_addr b = map_base;
00109     unsigned send_order = order;
00110     l4_ret_t err = map_hook(offset /*map_base - _ds_start*/, order, flags,
00111                             &b, &send_order);
00112     if (err < 0)
00113         return err;
00114
00115     l4_fpage_t fpage = l4_fpage(b, send_order, flags.fpage_rights());
00116
00117     memory = L4::Ipc::Snd_fpage(fpage, local_addr, _map_flags, _cache_flags);
00118
00119     return L4_EOK;
00120 }
00121
00136 virtual l4_ret_t map_hook([[maybe_unused]] Dataspace::Offset offs,
00137                           [[maybe_unused]] unsigned order,
00138                           [[maybe_unused]] Dataspace::Flags flags,
00139                           [[maybe_unused]] Dataspace::Map_addr *base,
00140                           [[maybe_unused]] unsigned *send_order)
00141 {
00142     return 0;
00143 }
00144
00150 virtual void take() noexcept
00151 {}
00152
00160 virtual unsigned long release() noexcept
00161 { return 0; }
00162
00175 virtual l4_ret_t copy([[maybe_unused]] l4_addr_t dst_offs,
00176                       [[maybe_unused]] l4_umword_t src_id,
00177                       [[maybe_unused]] l4_addr_t src_offs,
00178                       [[maybe_unused]] unsigned long size) noexcept
00179 {
00180     return -L4_ENODEV;
00181 }
00182
00192 virtual l4_ret_t clear(unsigned long offs, unsigned long size) const noexcept
00193 {
00194     if (!check_limit(offs))
00195         return -L4_ERANGE;
00196
00197     unsigned long sz = size = cxx::min(size, round_size() - offs);
00198
00199     while (sz)
00200     {
00201         unsigned long b_addr = _ds_start + offs;
00202         unsigned long b_sz = cxx::min(size - offs, sz);
00203
00204         memset(reinterpret_cast<void *>(b_addr), 0, b_sz);
00205     }

```

```

00206         offs += b_sz;
00207         sz -= b_sz;
00208     }
00209
00210     return 0;
00211 }
00212
00224 virtual l4_ret_t allocate([[maybe_unused]] l4_addr_t offset,
00225                          [[maybe_unused]] l4_size_t size,
00226                          [[maybe_unused]] unsigned access) noexcept
00227 {
00228     return -L4_ENODEV;
00229 }
00230
00236 virtual unsigned long page_shift() const noexcept
00237 { return L4_LOG2_PAGESIZE; }
00238
00244 virtual bool is_static() const noexcept
00245 { return true; }
00246
00259 virtual l4_ret_t map_info([[maybe_unused]] l4_addr_t &start_addr,
00260                          [[maybe_unused]] l4_addr_t &end_addr) noexcept
00261 { return -L4_EPERM; }
00262
00263
00264 l4_ret_t op_map(L4Re::Dataspace::Rights rights,
00265                L4Re::Dataspace::Offset offset,
00266                L4Re::Dataspace::Map_addr spot,
00267                L4Re::Dataspace::Flags flags,
00268                L4::Ipc::Snd_fpage &fp)
00269 {
00270     auto rf = map_flags(rights);
00271     if (!rf.w() && flags.w())
00272         return -L4_EPERM;
00273
00274     return map(offset, spot, flags & rf, 0, ~0, fp);
00275 }
00276
00277 l4_ret_t op_allocate(L4Re::Dataspace::Rights rights,
00278                     L4Re::Dataspace::Offset offset,
00279                     L4Re::Dataspace::Size size)
00280 { return allocate(offset, size, rights & 3); }
00281
00282 l4_ret_t op_copy_in(L4Re::Dataspace::Rights rights,
00283                    L4Re::Dataspace::Offset dst_offs,
00284                    L4::Ipc::Snd_fpage const &src_cap,
00285                    L4Re::Dataspace::Offset src_offs,
00286                    L4Re::Dataspace::Size sz)
00287 {
00288     if (!src_cap.id_received())
00289         return -L4_EINVAL;
00290
00291     if (!(rights & L4_CAP_FPAGE_W))
00292         return -L4_EACCESS;
00293
00294     if (sz == 0)
00295         return L4_EOK;
00296
00297     return copy(dst_offs, src_cap.data(), src_offs, sz);
00298 }
00299
00300 l4_ret_t op_info(L4Re::Dataspace::Rights rights, L4Re::Dataspace::Stats &s)
00301 {
00302     s.size = size();
00303     // only return writable if really writable
00304     s.flags = Dataspace::Flags(0);
00305     if (map_flags(rights).w())
00306         s.flags |= Dataspace::F::W;
00307     return L4_EOK;
00308 }
00309
00310 l4_ret_t op_clear(L4Re::Dataspace::Rights rights,
00311                  L4Re::Dataspace::Offset offset,
00312                  L4Re::Dataspace::Size size)
00313 {
00314     if (!map_flags(rights).w())
00315         return -L4_EACCESS;
00316
00317     return clear(offset, size);
00318 }
00319
00320 l4_ret_t op_map_info(L4Re::Dataspace::Rights,
00321                     [[maybe_unused]] l4_addr_t &start_addr,
00322                     [[maybe_unused]] l4_addr_t &end_addr)
00323 {
00324 #ifdef CONFIG_MMU
00325     return 0;

```

```

00326 #else
00327     return map_info(start_addr, end_addr);
00328 #endif
00329 }
00330
00331 protected:
00332     unsigned long size() const noexcept
00333     { return _ds_size; }
00334     unsigned long map_flags() const noexcept
00335     { return _map_flags; }
00336     unsigned long page_size() const noexcept
00337     { return 1UL < page_shift(); }
00338     unsigned long round_size() const noexcept
00339     { return l4_round_size(size(), page_shift()); }
00340     bool check_limit(l4_addr_t offset) const noexcept
00341     { return offset < round_size(); }
00342
00343     L4Re::Dataspace::Flags
00344     map_flags(L4Re::Dataspace::Rights rights = L4_CAP_FPAGE_W) const noexcept
00345     {
00346         auto f = (_rw_flags & L4Re::Dataspace::Flags(0x0f)) | L4Re::Dataspace::F::Caching_mask;
00347         if (!(rights & L4_CAP_FPAGE_W))
00348             f -= L4Re::Dataspace::F::W;
00349
00350         return f;
00351     }
00352
00353 protected:
00354     void size(unsigned long size) noexcept { _ds_size = size; }
00355
00356     l4_addr_t _ds_start;
00357     l4_size_t _ds_size;
00358     Map_type _map_flags;
00359     Cache_type _cache_flags;
00360     L4Re::Dataspace::Flags _rw_flags;
00361 };
00362
00363 {}

```

## 16.381 l4/re/debug File Reference

Debug interface.

```

#include <l4/sys/capability>
#include <l4/re/protocols.h>
#include <l4/sys/cxx/ipc_iface>

```



## 16.382 debug

[Go to the documentation of this file.](#)

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00006 /*
00007  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00008  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00009  *      economic rights: Technische Universität Dresden (Germany)
00010  *
00011  * License: see LICENSE.spdx (in this directory or the directories above)
00012  */
00013 #pragma once
00014
00015 #include <l4/sys/capability>
00016 #include <l4/re/protocols.h>
00017 #include <l4/sys/cxx/ipc_iface>
00018
00019 namespace L4Re {
00033
00040 class L4_EXPORT Debug_obj :
00041     public L4::Kobject_t<Debug_obj, L4::Kobject, L4RE_PROTO_DEBUG>
00042 {
00043 public:
00044
00056     L4_INLINE_RPC(l4_ret_t, debug, (unsigned long function));
00057     typedef L4::Typeid::Rpc_nocode<debug_t> Rpc;
00058 };
00059
00060 template<typename BASE>
00061 class Debug_obj_t :
00062     public L4::Kobject_2t<Debug_obj_t<BASE>, BASE, Debug_obj, L4::PROTO_EMPTY>
00063 {
00064     typedef L4::Typeid::Rpc<> Rpc;
00065 };
00066 }

```

## 16.383 debug

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00007 /*
00008  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00009  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00010  *      economic rights: Technische Universität Dresden (Germany)
00011  *
00012  * License: see LICENSE.spdx (in this directory or the directories above)
00013  */
00014 #pragma once
00015
00016 #include <l4/sys/types.h>
00017
00018 namespace L4Re { namespace Util {
00019 class Err
00020 {
00021 public:
00022     enum Level
00023     {
00024         Normal = 0,
00025         Fatal,
00026     };
00027
00028     static char const *const levels[];
00029
00030     void tag() const
00031     { printf("%s: %s", _component, levels[_l]); }
00032
00033     int printf(char const *fmt, ...) const
00034         __attribute__((format(printf,2,3)));
00035
00036     int cprintf(char const *fmt, ...) const
00037         __attribute__((format(printf,2,3)));
00038
00039     constexpr Err(Level l, char const *component) : _l(l), _component(component)
00040     {}
00041
00042 private:
00043     Level _l;
00044     char const *_component;
00045 };
00046
00047

```

```

00048 class Dbg
00049 {
00050 private:
00051     void tag() const;
00052
00053 #ifndef NDEBUG
00054
00055     unsigned long _m;
00056     char const *const _component;
00057     char const *const _subsys;
00058
00059 # ifnndef __clang__
00060
00061     int printf_impl(char const *fmt, ...) const
00062         __attribute__((format(printf, 2, 3)));
00063
00064     int cprintf_impl(char const *fmt, ...) const
00065         __attribute__((format(printf, 2, 3)));
00066
00067 # endif
00068
00069 public:
00070     static unsigned long level;
00071
00072     static void set_level(unsigned long l) { level = l; }
00073
00074     bool is_active() const { return _m & level; }
00075
00076 # ifdef __clang__
00077
00078     int printf(char const *fmt, ...) const
00079         __attribute__((format(printf, 2, 3)));
00080
00081     int cprintf(char const *fmt, ...) const
00082         __attribute__((format(printf, 2, 3)));
00083
00084 # else
00085
00086     int __attribute__((always_inline, format(printf, 2, 3)))
00087     printf(char const *fmt, ...) const
00088     {
00089         if (!(level & _m))
00090             return 0;
00091
00092         return printf_impl(fmt, __builtin_va_arg_pack());
00093     }
00094
00095     int __attribute__((always_inline, format(printf, 2, 3)))
00096     cprintf(char const *fmt, ...) const
00097     {
00098         if (!(level & _m))
00099             return 0;
00100
00101         return cprintf_impl(fmt, __builtin_va_arg_pack());
00102     }
00103
00104 # endif
00105
00106     explicit constexpr
00107     Dbg() : _m(1), _component(0), _subsys(0) {}
00108
00109     explicit constexpr
00110     Dbg(unsigned long mask, char const *comp, char const *subs)
00111     : _m(mask), _component(comp), _subsys(subs)
00112     {}
00113
00114 #else
00115
00116 public:
00117     static void set_level(unsigned long) {}
00118     bool is_active() const { return false; }
00119
00120     int printf(char const * /*fmt*/, ...) const
00121         __attribute__((format(printf, 2, 3)))
00122     { return 0; }
00123
00124     int cprintf(char const * /*fmt*/, ...) const
00125         __attribute__((format(printf, 2, 3)))
00126     { return 0; }
00127
00128     explicit constexpr
00129     Dbg() {}
00130
00131     explicit constexpr
00132     Dbg(unsigned long, char const *, char const *) {}
00133
00134 #endif

```



```

00135
00136 };
00137
00138 }}
00139

```

## 16.384 env\_ns

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00002
00003 #pragma once
00004
00005 #include <l4/re/cap_alloc>
00006 #include <l4/re/util/cap_alloc>
00007 #include <l4/re/namespace>
00008 #include <l4/re/env>
00009 #include <string.h>
00010
00011 namespace L4Re { namespace Util {
00012
00013 class Env_ns
00014 {
00015 private:
00016     L4Re::Cap_alloc *_ca;
00017     Env const *_env;
00018
00019 public:
00020     explicit Env_ns(Env const *env = Env::env(),
00021                    L4Re::Cap_alloc *ca = &L4Re::Util::cap_alloc)
00022         : _ca(ca), _env(env) {}
00023
00024     L4::Cap<void>
00025     query(char const *name, unsigned len, int timeout = Namespace::To_default,
00026           l4_umword_t *local_id = 0, bool iterate = true) const noexcept
00027     {
00028         typedef Env::Cap_entry Cap_entry;
00029
00030         // Skip possible first slash
00031         if (len && name[0] == '/')
00032         {
00033             ++name;
00034             --len;
00035         }
00036
00037         char const *n = name;
00038         for (; len && *n != '/'; ++n, --len) // Count first path element
00039             ;
00040
00041         Cap_entry const *e = _env->get(name, n - name);
00042         if (!e)
00043             return L4::Cap<void>(-L4_ENOENT);
00044
00045         if (len > 0 && *n == '/')
00046         {
00047             L4::Cap<L4Re::Namespace> ns(e->cap);
00048             L4::Cap<void> cap = _ca->alloc<void>();
00049
00050             if (!cap.is_valid())
00051                 return L4::Cap<void>(-L4_ENOMEM);
00052
00053             long r = ns->query(n + 1, len - 1, cap, timeout, local_id, iterate);
00054             if (r >= 0)
00055                 return cap;
00056
00057             _ca->free(cap);
00058
00059             return L4::Cap<void>(r);
00060         }
00061
00062         return L4::Cap<void>(e->cap);
00063     }
00064
00065     L4::Cap<void>
00066     query(char const *name, int timeout = Namespace::To_default,
00067           l4_umword_t *local_id = 0, bool iterate = true) const noexcept
00068     { return query(name, __builtin_strlen(name), timeout, local_id, iterate); }
00069
00070     template<typename T >
00071     L4::Cap<T>
00072     query(char const *name, int timeout = Namespace::To_default,
00073           l4_umword_t *local_id = 0, bool iterate = true) const noexcept
00074     {
00075         return L4::cap_cast<T>(query(name, __builtin_strlen(name),

```

```

00076                                     timeout, local_id, iterate));
00077     }
00078 };
00079
00080 }}

```

## 16.385 event

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00002 /*
00003  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00004  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00005  *      economic rights: Technische Universität Dresden (Germany)
00006  *
00007  * License: see LICENSE.spdx (in this directory or the directories above)
00008  */
00009
00010 #pragma once
00011
00012 #include <l4/sys/capability>
00013 #include <l4/sys/irq>
00014 #include <l4/sys/cxx/ipc_iface>
00015 #include <l4/sys/cxx/ipc_array>
00016 #include <l4/re/dataspace>
00017 #include <l4/re/event.h>
00018
00019 namespace L4Re {
00020
00021
00022
00023
00024 typedef l4re_event_stream_id_t Event_stream_id;
00025 typedef l4re_event_absinfo_t Event_absinfo;
00026
00027 class L4_EXPORT Event_stream_bitmap_h
00028 {
00029 protected:
00030     static unsigned __get_idx(unsigned idx)
00031     { return idx / (sizeof(unsigned long)*8); }
00032
00033     static unsigned long __get_mask(unsigned idx)
00034     { return 1ul << (idx % (sizeof(unsigned long)*8)); }
00035
00036     static bool __get_bit(unsigned long const *bm, unsigned max, unsigned idx)
00037     {
00038         if (idx <= max)
00039             return bm[__get_idx(idx)] & __get_mask(idx);
00040         return false;
00041     }
00042
00043     static void __set_bit(unsigned long *bm, unsigned max, unsigned idx, bool v)
00044     {
00045         if (idx > max)
00046             return;
00047
00048         if (v)
00049             bm[__get_idx(idx)] |= __get_mask(idx);
00050         else
00051             bm[__get_idx(idx)] &= ~__get_mask(idx);
00052     }
00053 };
00054
00055 class L4_EXPORT Event_stream_info
00056 : public l4re_event_stream_info_t,
00057   private Event_stream_bitmap_h
00058 {
00059 public:
00060     bool get_propbit(unsigned idx) const
00061     { return __get_bit(propbits, L4RE_EVENT_PROP_MAX, idx); }
00062
00063     void set_propbit(unsigned idx, bool v)
00064     { __set_bit(propbits, L4RE_EVENT_PROP_MAX, idx, v); }
00065
00066     bool get_evbit(unsigned idx) const
00067     { return __get_bit(evbits, L4RE_EVENT_EV_MAX, idx); }
00068
00069     void set_evbit(unsigned idx, bool v)
00070     { __set_bit(evbits, L4RE_EVENT_EV_MAX, idx, v); }
00071
00072     bool get_keybit(unsigned idx) const
00073     { return __get_bit(keybits, L4RE_EVENT_KEY_MAX, idx); }
00074
00075     void set_keybit(unsigned idx, bool v)
00076     { __set_bit(keybits, L4RE_EVENT_KEY_MAX, idx, v); }
00077
00078
00079
00080
00081
00082
00083
00084
00085
00086
00087
00088
00089
00090
00091
00092
00093

```

```

00094 bool get_relbit(unsigned idx) const
00095 { return __get_bit(relbits, L4RE_EVENT_REL_MAX, idx); }
00096
00097 void set_relbit(unsigned idx, bool v)
00098 { __set_bit(relbits, L4RE_EVENT_REL_MAX, idx, v); }
00099
00100 bool get_absbit(unsigned idx) const
00101 { return __get_bit(absbits, L4RE_EVENT_ABS_MAX, idx); }
00102
00103 void set_absbit(unsigned idx, bool v)
00104 { __set_bit(absbits, L4RE_EVENT_ABS_MAX, idx, v); }
00105
00106 bool get_swbit(unsigned idx) const
00107 { return __get_bit(swbits, L4RE_EVENT_SW_MAX, idx); }
00108
00109 void set_swbit(unsigned idx, bool v)
00110 { __set_bit(swbits, L4RE_EVENT_SW_MAX, idx, v); }
00111 };
00112
00113 class L4_EXPORT Event_stream_state
00114 : public l4re_event_stream_state_t,
00115 private Event_stream_bitmap_h
00116 {
00117 public:
00118 bool get_keybit(unsigned idx) const
00119 { return __get_bit(keybits, L4RE_EVENT_KEY_MAX, idx); }
00120
00121 void set_keybit(unsigned idx, bool v)
00122 { __set_bit(keybits, L4RE_EVENT_KEY_MAX, idx, v); }
00123
00124 bool get_swbit(unsigned idx) const
00125 { return __get_bit(swbits, L4RE_EVENT_SW_MAX, idx); }
00126
00127 void set_swbit(unsigned idx, bool v)
00128 { __set_bit(swbits, L4RE_EVENT_SW_MAX, idx, v); }
00129 };
00130
00137 class L4_EXPORT Event :
00138 public L4::Kobject_t<Event, L4::Icu, L4RE_PROTO_EVENT>
00139 {
00140 public:
00149 L4_RPC(l4_ret_t, get_buffer, (L4::Ipc::Out<L4::Cap<Dataspace>> ds));
00150
00157 L4_RPC(l4_ret_t, get_num_streams, ());
00158
00170 L4_RPC(l4_ret_t, get_stream_info, (int idx, Event_stream_info *info));
00171
00181 L4_RPC(l4_ret_t, get_stream_info_for_id, (l4_umword_t stream_id, Event_stream_info *info));
00182
00194 L4_RPC_NF(l4_ret_t, get_axis_info, (l4_umword_t stream_id,
00195                                     L4::Ipc::Array<unsigned const,
00196                                     unsigned long> axes,
00197                                     L4::Ipc::Array<Event_absinfo,
00198                                     unsigned long> &info));
00199
00200 l4_ret_t get_axis_info(l4_umword_t stream_id, unsigned naxes,
00201                       unsigned const *axis, Event_absinfo *info) const noexcept
00202 {
00203     L4::Ipc::Array<Event_absinfo, unsigned long> i(naxes, info);
00204     return get_axis_info_t::call(c(), stream_id,
00205                                   L4::Ipc::Array<unsigned const, unsigned long>(naxes, axis), i);
00206 }
00207
00217 L4_RPC(l4_ret_t, get_stream_state_for_id, (l4_umword_t stream_id,
00218                                           Event_stream_state *state));
00219
00220 typedef L4::TypeId::Rpc<
00221     get_buffer_t,
00222     get_num_streams_t,
00223     get_stream_info_t,
00224     get_stream_info_for_id_t,
00225     get_axis_info_t,
00226     get_stream_state_for_id_t
00227 > Rpc<
00228 >;
00229
00234 struct L4_EXPORT Default_event_payload
00235 {
00236     unsigned short type;
00237     unsigned short code;
00238     int value;
00239     l4_umword_t stream_id;
00240 };
00241
00242
00247 template< typename PAYLOAD = Default_event_payload >
00248 class L4_EXPORT Event_buffer_t

```

```

00249 {
00250 public:
00251
00255     struct Event
00256     {
00257         long long time;
00258         PAYLOAD payload;
00259
00263         void free() noexcept { l4_mb(); time = 0; }
00264     };
00265
00266 private:
00267     Event *_current;
00268     Event *_begin;
00269     Event const *_end;
00270
00271     void inc() noexcept
00272     {
00273         ++_current;
00274         if (_current == _end)
00275             _current = _begin;
00276     }
00277
00278 public:
00279
00280     Event_buffer_t() : _current(0), _begin(0), _end(0) {}
00281
00282     void reset()
00283     {
00284         for (Event *i = _begin; i != _end; ++i)
00285             i->time = 0;
00286         _current = _begin;
00287     }
00288
00295     Event_buffer_t(void *buffer, l4_addr_t size)
00296     : _current(static_cast<Event*>(buffer)), _begin(_current),
00297       _end(_begin + size / sizeof(Event))
00298     { reset(); }
00299
00305     Event *next() noexcept
00306     {
00307         Event *c = _current;
00308         if (c->time)
00309         {
00310             inc();
00311             return c;
00312         }
00313         return 0;
00314     }
00315
00322     bool put(Event const &ev) noexcept
00323     {
00324         Event *c = _current;
00325         if (c->time)
00326             return false;
00327
00328         inc();
00329         c->payload = ev.payload;
00330         l4_wmb();
00331         c->time = ev.time;
00332         return true;
00333     }
00334 };
00335
00336 typedef Event_buffer_t<Default_event_payload> Event_buffer;
00337
00338 }

```


## 16.386 l4/re/util/event File Reference

```

#include <l4/re/cap_alloc>
#include <l4/re/util/cap_alloc>
#include <l4/re/util/unique_cap>
#include <l4/re/env>
#include <l4/re/rm>
#include <l4/re/util/event_buffer>
#include <l4/sys/factory>

```

```
#include <l4/cxx/type_traits>
Include dependency graph for event:
```



## Data Structures

- class [L4Re::Util::Event\\_t< PAYLOAD >](#)  
*Convenience wrapper for getting access to an event object.*

## Namespaces

- namespace [L4Re](#)  
*L4Re C++ Interfaces.*
- namespace [L4Re::Util](#)  
*Documentation of the [L4 Runtime Environment](#) utility functionality in C++.*

## 16.387 event

[Go to the documentation of this file.](#)

```
00001 // vi:set ft=cpp: -- Mode: C++ --
00002 /*
00003  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00004  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00005  *      economic rights: Technische Universität Dresden (Germany)
00006  *
00007  * License: see LICENSE.spdx (in this directory or the directories above)
00008  */
00009 #pragma once
00010
00011 #include <l4/re/cap_alloc>
00012 #include <l4/re/util/cap_alloc>
00013 #include <l4/re/util/unique_cap>
00014 #include <l4/re/env>
00015 #include <l4/re/rm>
00016 #include <l4/re/util/event_buffer>
00017 #include <l4/sys/factory>
00018 #include <l4/cxx/type_traits>
00019
00020 namespace L4Re { namespace Util {
00021
00022     template< typename PAYLOAD >
00023     class Event_t
00024     {
00025     public:
```

```

00038 enum Mode
00039 {
00040     Mode_irq,
00041     Mode_polling,
00042 };
00043
00058 template<typename IRQ_TYPE>
00059 int init(L4::Cap<L4Re::Event> event,
00060         L4Re::Env const *env = L4Re::Env::env(),
00061         L4Re::Cap_alloc *ca = &L4Re::Util::cap_alloc)
00062 {
00063     Unique_cap<L4Re::Dataspace> ev_ds(ca->alloc<L4Re::Dataspace>());
00064     if (!ev_ds.is_valid())
00065         return -L4_ENOMEM;
00066
00067     int r;
00068
00069     Unique_del_cap<IRQ_TYPE> ev_irq(ca->alloc<IRQ_TYPE>());
00070     if (!ev_irq.is_valid())
00071         return -L4_ENOMEM;
00072
00073     if ((r = l4_error(env->factory()->create(ev_irq.get()))))
00074         return r;
00075
00076     if ((r = l4_error(event->bind(0, ev_irq.get()))))
00077         return r;
00078
00079     if ((r = event->get_buffer(ev_ds.get())))
00080         return r;
00081
00082     long sz = ev_ds->size();
00083     if (sz < 0)
00084         return sz;
00085
00086     Rm::Unique_region<void*> buf;
00087
00088     if ((r = env->rm()->attach(&buf, sz,
00089                             L4Re::Rm::F::Search_addr | L4Re::Rm::F::RW,
00090                             L4::Ipc::make_cap_rw(ev_ds.get()))))
00091         return r;
00092
00093     _ev_buffer = L4Re::Event_buffer_t<PAYLOAD>(buf.get(), sz);
00094     _ev_ds      = cxx::move(ev_ds);
00095     _ev_irq     = cxx::move(ev_irq);
00096     _buf        = cxx::move(buf);
00097
00098     return 0;
00099 }
00100
00112 int init_poll(L4::Cap<L4Re::Event> event,
00113              L4Re::Env const *env = L4Re::Env::env(),
00114              L4Re::Cap_alloc *ca = &L4Re::Util::cap_alloc)
00115 {
00116     Unique_cap<L4Re::Dataspace> ev_ds(ca->alloc<L4Re::Dataspace>());
00117     if (!ev_ds.is_valid())
00118         return -L4_ENOMEM;
00119
00120     int r;
00121
00122     if ((r = event->get_buffer(ev_ds.get())))
00123         return r;
00124
00125     long sz = ev_ds->size();
00126     if (sz < 0)
00127         return sz;
00128
00129     Rm::Unique_region<void*> buf;
00130
00131     if ((r = env->rm()->attach(&buf, sz,
00132                             L4Re::Rm::F::Search_addr | L4Re::Rm::F::RW,
00133                             L4::Ipc::make_cap_rw(ev_ds.get()))))
00134         return r;
00135
00136     _ev_buffer = L4Re::Event_buffer_t<PAYLOAD>(buf.get(), sz);
00137     _ev_ds      = cxx::move(ev_ds);
00138     _buf        = cxx::move(buf);
00139
00140     return 0;
00141 }
00142
00148 L4Re::Event_buffer_t<PAYLOAD> &buffer() { return _ev_buffer; }
00149
00155 L4::Cap<L4::Triggerable> irq() const { return _ev_irq.get(); }
00156
00157 private:
00158     Unique_cap<L4Re::Dataspace> _ev_ds;
00159     Unique_del_cap<L4::Triggerable> _ev_irq;

```

```

00160     L4Re::Event_buffer_t<PAYLOAD> _ev_buffer;
00161     Rm::Unique_region<void*> _buf;
00162 };
00163
00164 typedef Event_t<Default_event_payload> Event;
00165
00166 }}

```

## 16.388 event\_buffer

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00002 /*
00003  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00004  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00005  *      economic rights: Technische Universität Dresden (Germany)
00006  *
00007  * License: see LICENSE.spdx (in this directory or the directories above)
00008  */
00009
00010 #pragma once
00011
00012 #include <l4/re/event>
00013 #include <l4/re/event-sys.h>
00014 #include <l4/re/rm>
00015
00016 #include <string.h>
00017
00018 namespace L4Re { namespace Util {
00019
00020     template< typename PAYLOAD >
00021     class Event_buffer_t : public L4Re::Event_buffer_t<PAYLOAD>
00022     {
00023     private:
00024         void *_buf;
00025     public:
00026         void *_buf() const noexcept { return _buf; }
00027
00028         long attach(L4::Cap<L4Re::Dataspace> ds, L4::Cap<L4Re::Rm> rm) noexcept
00029         {
00030             l4_addr_t sz = ds->size();
00031             _buf = 0;
00032
00033             long r = rm->attach(&_buf, sz,
00034                               L4Re::Rm::F::Search_addr | L4Re::Rm::F::RW,
00035                               L4::Ipc::make_cap_rw(ds));
00036
00037             if (r < 0)
00038                 return r;
00039
00040             *static_cast<L4Re::Event_buffer_t<PAYLOAD>*>(this)
00041               = L4Re::Event_buffer_t<PAYLOAD>(_buf, sz);
00042             return 0;
00043         }
00044
00045         long detach(L4::Cap<L4Re::Rm> rm) noexcept
00046         {
00047             L4::Cap<L4Re::Dataspace> ds;
00048             if (_buf)
00049                 return rm->detach(_buf, &ds);
00050             return 0;
00051         }
00052     };
00053
00054     template< typename PAYLOAD >
00055     class Event_buffer_consumer_t : public Event_buffer_t<PAYLOAD>
00056     {
00057     public:
00058         template< typename CB, typename D >
00059         void foreach_available_event(CB const &cb, D data = D())
00060         {
00061             typename Event_buffer_t<PAYLOAD>::Event *e;
00062             while ((e = Event_buffer_t<PAYLOAD>::next()))
00063             {
00064                 cb(e, data);
00065                 e->free();
00066             }
00067         }
00068
00069         template< typename CB, typename D >
00070         void process(L4::Cap<L4::Irq> irq,
00071                    L4::Cap<L4::Thread> thread,
00072                    CB const &cb, D data = D())
00073         {
00074         }
00075     };
00076 }
00077
00078 template< typename PAYLOAD >
00079 class Event_buffer_consumer_t : public Event_buffer_t<PAYLOAD>
00080 {
00081 public:
00082     template< typename CB, typename D >
00083     void foreach_available_event(CB const &cb, D data = D())
00084     {
00085         typename Event_buffer_t<PAYLOAD>::Event *e;
00086         while ((e = Event_buffer_t<PAYLOAD>::next()))
00087         {
00088             cb(e, data);
00089             e->free();
00090         }
00091     }
00092
00093     template< typename CB, typename D >
00094     void process(L4::Cap<L4::Irq> irq,
00095                 L4::Cap<L4::Thread> thread,
00096                 CB const &cb, D data = D())
00097     {
00098     }
00099 }

```

```

00118 {
00119
00120     if (l4_error(irq->bind_thread(thread, 0)))
00121         return;
00122
00123     while (1)
00124     {
00125         long r;
00126         r = l4_ipc_error(l4_irq_receive(irq.cap(), L4_IPC_NEVER),
00127                         l4_utcb());
00128         if (r)
00129             continue;
00130
00131         foreach_available_event(cb, data);
00132     }
00133 }
00134 };
00135
00136 typedef Event_buffer_t<Default_event_payload> Event_buffer;
00137 typedef Event_buffer_consumer_t<Default_event_payload> Event_buffer_consumer;
00138
00139 }}

```

## 16.389 event\_svr

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00002 /*
00003  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00004  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00005  *      economic rights: Technische Universität Dresden (Germany)
00006  *
00007  * License: see LICENSE.spdx (in this directory or the directories above)
00008  */
00009
00010 #pragma once
00011
00012 #include <l4/re/event_enums.h>
00013 #include <l4/re/event>
00014 #include <l4/re/event-sys.h>
00015 #include <l4/re/util/icu_svr>
00016 #include <l4/cxx/minmax>
00017
00018 #include <l4/sys/cxx/ipc_legacy>
00019
00020 namespace L4Re { namespace Util {
00021
00022     template< typename SVR >
00023     class Event_svr : public Icu_cap_array_svr<SVR>
00024     {
00025     private:
00026         typedef Icu_cap_array_svr<SVR> Icu_svr;
00027
00028     protected:
00029         L4::Cap<L4Re::Dataspace> _ds;
00030         typename Icu_svr::Irq _irq;
00031
00032     public:
00033         Event_svr() : Icu_svr(1, &_irq) {}
00034
00035         L4_RPC_LEGACY_DISPATCH(L4Re::Event);
00036         L4_RPC_LEGACY_USING(Icu_svr);
00037
00038         l4_ret_t op_get_buffer(L4Re::Event::Rights, L4::Ipc::Cap<L4Re::Dataspace> &ds)
00039         {
00040             static_cast<SVR*>(this)->reset_event_buffer();
00041             ds = L4::Ipc::Cap<L4Re::Dataspace>(_ds, L4_CAP_FPAGE_RW);
00042             return 0;
00043         }
00044
00045         l4_ret_t op_get_num_streams(L4Re::Event::Rights)
00046         { return static_cast<SVR*>(this)->get_num_streams(); }
00047
00048         l4_ret_t op_get_stream_info(L4Re::Event::Rights, int idx, Event_stream_info &info)
00049         { return static_cast<SVR*>(this)->get_stream_info(idx, &info); }
00050
00051         l4_ret_t op_get_stream_info_for_id(L4Re::Event::Rights, l4_umword_t id,
00052                                           Event_stream_info &info)
00053         { return static_cast<SVR*>(this)->get_stream_info_for_id(id, &info); }
00054
00055         l4_ret_t op_get_axis_info(L4Re::Event::Rights, l4_umword_t id,
00056                                  L4::Ipc::Array_in_buf<unsigned, unsigned long> const &axes,
00057                                  L4::Ipc::Array_ref<Event_absinfo, unsigned long> &info)
00058         {

```



```

00065     unsigned naxes = cxx::min<unsigned>(L4RE_ABS_MAX, axes.length);
00066
00067     info.length = 0;
00068
00069     Event_absinfo _info[L4RE_ABS_MAX];
00070     int r = static_cast<SVR*>(this)->get_axis_info(id, naxes, axes.data, _info);
00071     if (r < 0)
00072         return r;
00073
00074     for (unsigned i = 0; i < naxes; ++i)
00075         info.data[i] = _info[i];
00076
00077     info.length = naxes;
00078     return r;
00079 }
00080
00081 l4_ret_t op_get_stream_state_for_id(L4Re::Event::Rights, l4_umword_t stream_id,
00082                                     Event_stream_state &state)
00083 { return static_cast<SVR*>(this)->get_stream_state_for_id(stream_id, &state); }
00084
00085 int get_num_streams() const { return 0; }
00086 int get_stream_info(int, L4Re::Event_stream_info *)
00087 { return -L4_EINVAL; }
00088 int get_stream_info_for_id(l4_umword_t, L4Re::Event_stream_info *)
00089 { return -L4_EINVAL; }
00090 int get_axis_info(l4_umword_t, unsigned /*naxes*/, unsigned const * /*axes*/,
00091                  L4Re::Event_absinfo *)
00092 { return -L4_EINVAL; }
00093 int get_stream_state_for_id(l4_umword_t, L4Re::Event_stream_state *)
00094 { return -L4_EINVAL; }
00095 };
00096
00097 }}

```

## 16.390 icu\_svr

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00002 /*
00003  * (c) 2009-2014 Alexander Warg <alexander.warg@kernkonzept.com>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007
00008 #pragma once
00009
00010
00011 #include <l4/sys/types.h>
00012
00013 #include <l4/sys/icu>
00014 #include <l4/sys/task>
00015 #include <l4/re/env>
00016 #include <l4/re/util/cap_alloc>
00017 #include <l4/sys/cxx/ipc_legacy>
00018
00019 namespace L4Re { namespace Util {
00020
00021     template< typename ICU >
00022     class Icu_svr
00023     {
00024     private:
00025         ICU const *this_icu() const { return static_cast<ICU const *>(this); }
00026         ICU *this_icu() { return static_cast<ICU*>(this); }
00027
00028     public:
00029         L4_RPC_LEGACY_DISPATCH(L4::Icu);
00030
00031         l4_ret_t op_bind(L4::Icu::Rights, l4_umword_t irqnum,
00032                         L4::Ipc::Snd_fpage irq_fp);
00033         l4_ret_t op_unbind(L4::Icu::Rights, l4_umword_t irqnum,
00034                           L4::Ipc::Snd_fpage irq_fp);
00035         l4_ret_t op_info(L4::Icu::Rights, L4::Icu::_Info &info);
00036         l4_ret_t op_msi_info(L4::Icu::Rights, l4_umword_t irqnum,
00037                             l4_uint64_t source, l4_icu_msi_info_t &info);
00038         l4_ret_t op_mask(L4::Icu::Rights, l4_umword_t irqnum);
00039         l4_ret_t op_unmask(L4::Icu::Rights, l4_umword_t irqnum);
00040         l4_ret_t op_set_mode(L4::Icu::Rights, l4_umword_t, l4_umword_t)
00041         { return 0; }
00042     };
00043
00044     template<typename ICU> inline
00045     l4_ret_t
00046     Icu_svr<ICU>::op_bind(L4::Icu::Rights, l4_umword_t irqnum,
00047                           L4::Ipc::Snd_fpage irq_fp)

```

```

00048 {
00049     typename ICU::Irq *irq = this_icu()->icu_get_irq(irqnum);
00050     if (!irq)
00051         return -L4_EINVAL;
00052
00053     return irq->bind(this_icu(), irq_fp);
00054 }
00055
00056 template<typename ICU> inline
00057 l4_ret_t
00058 Icu_svr<ICU>::op_unbind(L4::Icu::Rights, l4_umword_t irqnum,
00059                        L4::Ipc::Snd_fpage irq_fp)
00060 {
00061     typename ICU::Irq *irq = this_icu()->icu_get_irq(irqnum);
00062     if (!irq)
00063         return -L4_EINVAL;
00064
00065     return irq->unbind(this_icu(), irq_fp);
00066 }
00067
00068 template<typename ICU> inline
00069 l4_ret_t
00070 Icu_svr<ICU>::op_info(L4::Icu::Rights, L4::Icu::_Info &info)
00071 {
00072     l4_icu_info_t i;
00073     this_icu()->icu_get_info(&i);
00074     info.features = i.features;
00075     info.nr_irqs = i.nr_irqs;
00076     info.nr_msis = i.nr_msis;
00077     return 0;
00078 }
00079
00080 template<typename ICU> inline
00081 l4_ret_t
00082 Icu_svr<ICU>::op_msi_info(L4::Icu::Rights, l4_umword_t irqnum,
00083                          l4_uint64_t source, l4_icu_msi_info_t &info)
00084 {
00085     typename ICU::Irq *irq = this_icu()->icu_get_irq(irqnum);
00086     if (!irq)
00087         return -L4_EINVAL;
00088     return irq->msi_info(source, &info);
00089 }
00090
00091 template<typename ICU> inline
00092 l4_ret_t
00093 Icu_svr<ICU>::op_mask(L4::Icu::Rights, l4_umword_t irqnum)
00094 {
00095     typename ICU::Irq *irq = this_icu()->icu_get_irq(irqnum);
00096     if (irq)
00097         irq->mask(true);
00098     return -L4_ENOREPLY;
00099 }
00100
00101 template<typename ICU> inline
00102 l4_ret_t
00103 Icu_svr<ICU>::op_unmask(L4::Icu::Rights, l4_umword_t irqnum)
00104 {
00105     typename ICU::Irq *irq = this_icu()->icu_get_irq(irqnum);
00106     if (irq)
00107         irq->mask(false);
00108     return -L4_ENOREPLY;
00109 }
00110
00111
00112 template< typename ICU >
00113 class Icu_cap_array_svr : public Icu_svr<ICU>
00114 {
00115 protected:
00116     static void free_irq_cap(L4::Cap<L4::Irq> &cap)
00117     {
00118         if (cap)
00119         {
00120             L4Re::Util::cap_alloc.free(cap);
00121             cap.invalidate();
00122         }
00123     }
00124
00125 public:
00126     class Irq
00127     {
00128     public:
00129         Irq() {}
00130         ~Irq() { ICU::free_irq_cap(_cap); }
00131
00132         void trigger() const
00133         {
00134             if (_cap)

```

```

00135     _cap->trigger();
00136 }
00137
00138 l4_ret_t bind(ICU *, L4::Ipc::Snd_fpage const &irq_fp);
00139 l4_ret_t unbind(ICU *, L4::Ipc::Snd_fpage const &irq_fp);
00140 void mask(bool /*mask*/) const
00141 { }
00142
00143 l4_ret_t msi_info(l4_uint64_t, l4_icu_msi_info_t *) const
00144 { return -L4_EINVAL; }
00145
00146 L4::Cap<L4::Irq> cap() const { return _cap; }
00147
00148 private:
00149     L4::Cap<L4::Irq> _cap;
00150 };
00151
00152 private:
00153     Irq *_irqs;
00154     unsigned _nr_irqs;
00155
00156 public:
00157
00158     Icu_cap_array_svr(unsigned nr_irqs, Irq *irqs)
00159     : _irqs(irqs), _nr_irqs(nr_irqs)
00160     {}
00161
00162     Irq *icu_get_irq(l4_umword_t irqnum)
00163     {
00164         if (irqnum >= _nr_irqs)
00165             return 0;
00166
00167         return _irqs + irqnum;
00168     }
00169
00170     void icu_get_info(l4_icu_info_t *inf)
00171     {
00172         inf->features = 0;
00173         inf->nr_irqs = _nr_irqs;
00174         inf->nr_msis = 0;
00175     }
00176 };
00177
00178 template< typename ICU >
00179 l4_ret_t
00180 Icu_cap_array_svr<ICU>::Irq::bind(ICU *cfb, L4::Ipc::Snd_fpage const &irq_fp)
00181 {
00182     if (!irq_fp.cap_received())
00183         return -L4_EINVAL;
00184
00185     L4::Cap<L4::Irq> irq = cfb->server_iface()->template_rcv_cap<L4::Irq>(0);
00186     if (!irq)
00187         return -L4_EINVAL;
00188
00189     int r = cfb->server_iface()->realloc_rcv_cap(0);
00190     if (r < 0)
00191         return r;
00192
00193     ICU::free_irq_cap(_cap);
00194     _cap = irq;
00195     return 0;
00196 }
00197
00198 template< typename ICU >
00199 l4_ret_t
00200 Icu_cap_array_svr<ICU>::Irq::unbind(ICU *, L4::Ipc::Snd_fpage const &/*irq_fp*/)
00201 {
00202     ICU::free_irq_cap(_cap);
00203     _cap = L4::Cap<L4::Irq>::Invalid;
00204     return 0;
00205 }
00206
00207
00208 }


```

## 16.391 I4/re/util/item\_alloc File Reference


Item allocator.

```
#include <l4/cxx/bitmap>
```

Include dependency graph for item\_alloc:



This graph shows which files directly or indirectly include this file:



## Data Structures

- class [L4Re::Util::Item\\_alloc\\_base](#)  
*Item allocator.*
- class [L4Re::Util::Bitmap\\_base](#)  
*Basic bitmap abstraction.*
- class [L4Re::Util::Bitmap< BITS >](#)  
*A static bitmap.*

## Namespaces

- namespace [L4Re](#)  
*L4Re C++ Interfaces.*
- namespace [L4Re::Util](#)  
*Documentation of the [L4](#) Runtime Environment utility functionality in C++.*

## 16.391.1 Detailed Description

Item allocator.

Definition in file [item\\_alloc](#).

## 16.392 item\_alloc

[Go to the documentation of this file.](#)

```

00001 // -*- Mode: C++ -*-
00002 // vim:ft=cpp
00003 /*
00004  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00005  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00006  *      economic rights: Technische Universität Dresden (Germany)
00007  *
00008  * License: see LICENSE.spdx (in this directory or the directories above)
00009  */
00010
00011 #pragma once
00012
00013 #include <l4/cxx/bitmap>
00014
00015 namespace L4Re { namespace Util {
00016
00017     using cxx::Bitmap_base;
00018     using cxx::Bitmap;
00019
00020     class Item_alloc_base
00021     {
00022     private:
00023         long _capacity;
00024         long _free_hint;
00025         Bitmap_base _bits;
00026
00027         void hint(long hint)
00028         { __atomic_store_n(&_free_hint, hint, __ATOMIC_RELAXED); }
00029
00030     public:
00031         bool is_allocated(long item) const noexcept
00032         { return _bits[item]; }
00033
00034         long hint() const { return __atomic_load_n(&_free_hint, __ATOMIC_RELAXED); }
00035
00036         bool alloc(long item) noexcept
00037         {
00038             return !_bits.atomic_get_and_set(item);
00039         }
00040
00041         void free(long item) noexcept
00042         {
00043             if (item < hint())
00044                 hint(item);
00045
00046             _bits.atomic_clear_bit(item);
00047         }
00048
00049         Item_alloc_base(long size, void *mem) noexcept
00050             : _capacity(size), _free_hint(0), _bits(mem)
00051         {}
00052
00053         long alloc() noexcept
00054         {
00055             long free_hint = hint();
00056
00057             for (long i = free_hint; i < _capacity; ++i)
00058                 if (alloc(i))
00059                     hint(i + 1);
00060             return i;
00061         }
00062
00063         // _free_hint is not necessarily correct in case of multi-threading! Make
00064         // sure we don't miss any potentially free slots.
00065         for (long i = 0; i < free_hint && i < _capacity; ++i)
00066             if (alloc(i))
00067                 hint(i + 1);
00067     }
00068 }

```



### 16.393.1 Detailed Description

Kumem allocator helper.

Definition in file [kumem\\_alloc](#).

## 16.394 kumem\_alloc

[Go to the documentation of this file.](#)

```
00001 // -*- Mode: C++ -*-
00002 // vim:ft=cpp
00007 /*
00008  * (c) 2010 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00009  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00010  *      economic rights: Technische Universität Dresden (Germany)
00011  *
00012  * License: see LICENSE.spdx (in this directory or the directories above)
00013  */
00014
00015 #pragma once
00016
00017 #include <l4/re/env>
00018
00019 namespace L4Re { namespace Util {
00020
00026
00044 int
00045 kumem_alloc(l4_addr_t *mem, unsigned pages_order,
00046             L4::Cap<L4::Task> task = L4Re::Env::env()->task(),
00047             L4::Cap<L4Re::Rm> rm = L4Re::Env::env()->rm()) noexcept;
00048
00050 }}
```

## 16.395 name\_space\_svr

```
00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00002 /*
00003  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00004  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00005  *      economic rights: Technische Universität Dresden (Germany)
00006  *
00007  * License: see LICENSE.spdx (in this directory or the directories above)
00008  */
00009 #pragma once
00010
00011 #include <l4/cxx/avl_tree>
00012 #include <l4/cxx/std_ops>
00013 #include <l4/sys/cxx/ipc_epiface>
00014 #include <l4/cxx/string>
00015 #include <l4/re/util/debug>
00016
00017 #include <l4/sys/capability>
00018 #include <l4/re/namespace>
00019
00020 #include <stddef.h>
00021 #include <string.h>
00022
00023 namespace L4Re { namespace Util { namespace Names {
00024
00028 class Name : public cxx::String
00029 {
00030 public:
00031
00032     Name(const char *name = "") : String(name, __builtin_strlen(name)) {}
00033     Name(const char *name, unsigned long len) : String(name, len) {}
00034     Name(cxx::String const &n) : String(n) {}
00035     char const *name() const { return start(); }
00036     bool operator < (Name const &r) const
00037     {
00038         unsigned long l = cxx::min(len(), r.len());
00039         int v = memcmp(start(), r.start(), l);
00040         return v < 0 || (v == 0 && len() < r.len());
00041     }
00042 }
```

```

00042 };
00043
00044
00048 class Obj
00049 {
00050 protected:
00051     unsigned _f;
00052     union
00053     {
00054         l4_cap_idx_t _cap;
00055         L4::Epiface *_obj;
00056     };
00057
00058
00059 public:
00060     enum Flags
00061     {
00062         F_rw          = L4Re::Namespace::Rw,
00063         F_strong       = L4Re::Namespace::Strong,
00064
00065         F_trusted      = L4Re::Namespace::Trusted,
00066
00067         F_rights_mask = F_rw | F_strong | F_trusted,
00068
00069         F_cap          = 0x100,
00070         F_local        = 0x200,
00071         F_replacable   = 0x400,
00072         F_base_mask    = 0xf00,
00073     };
00074
00075
00076     unsigned flags() const { return _f; }
00077     void restrict_flags(unsigned max_rights)
00078     { _f &= (~F_rights_mask | (max_rights & F_rights_mask)); }
00079
00080     bool is_rw() const { return (_f & F_rw) == F_rw; }
00081     bool is_strong() const { return _f & F_strong; }
00082
00083     bool is_valid() const { return _f & F_cap; }
00084     bool is_complete() const { return is_valid(); }
00085     bool is_local() const { return _f & F_local; }
00086     bool is_replacable() const { return _f & F_replacable; }
00087     bool is_trusted() const { return _f & F_trusted; }
00088
00089     L4::Epiface *obj() const { if (is_local()) return _obj; return 0; }
00090     L4::Cap<void> cap() const
00091     {
00092         if (!is_local())
00093             return L4::Cap<void>(_cap);
00094         if (!_obj)
00095             return L4::Cap<void>::Invalid;
00096         return _obj->obj_cap();
00097     }
00098
00099
00100     void set(Obj const &o, unsigned flags)
00101     {
00102         *this = o;
00103         restrict_flags(flags);
00104     }
00105
00106     explicit Obj(unsigned flags = 0)
00107     : _f(flags), _cap(L4_INVALID_CAP)
00108     {}
00109
00110     Obj(unsigned f, L4::Cap<void> const &cap)
00111     : _f((f & ~F_base_mask) | F_cap), _cap(cap.cap())
00112     {}
00113
00114     Obj(unsigned f, L4::Epiface *o)
00115     : _f((f & ~F_base_mask) | F_cap | F_local), _obj(o)
00116     {}
00117
00118     void reset(unsigned flags)
00119     {
00120         _f = (_f & F_replacable) | (flags & ~(F_cap | F_local));
00121         _cap = L4_INVALID_CAP;
00122     }
00123
00124
00125 };
00126
00127
00131 class Entry : public cxx::Avl_tree_node
00132 {
00133 private:
00134     friend class Name_space;

```



```

00135     Name _n;
00136     Obj _o;
00137
00138     bool _dynamic;
00139
00140 public:
00141     Entry(Name const &n, Obj const &o, bool dynamic = false)
00142     : _n(n), _o(o), _dynamic(dynamic) {}
00143
00144     Name const &name() const { return _n; }
00145     Obj const *obj() const { return &_amp;o; }
00146     Obj *obj() { return &_amp;o; }
00147     void obj(Obj const &o) { _o = o; }
00148
00149     bool is_placeholder() const
00150     { return !obj()->is_complete(); }
00151
00152     bool is_dynamic() const { return _dynamic; }
00153
00154     void set(Obj const &o)
00155     {
00156         obj()->set(o, obj()->flags());
00157     }
00158
00159 private:
00160     void * operator new (size_t s);
00161     void operator delete(void *b);
00162
00163 };
00164
00165 struct Names_get_key
00166 {
00167     typedef Name Key_type;
00168     static Key_type const &key_of(Entry const *e)
00169     { return e->name(); }
00170 };
00171
00172
00180 class Name_space
00181 {
00182     friend class Entry;
00183
00184 private:
00185     typedef cxx::Avl_tree<Entry, Names_get_key> Tree;
00186     Tree _tree;
00187
00188 protected:
00189     L4Re::Util::Dbg const &_dbg;
00190     L4Re::Util::Err const &_err;
00191
00192 public:
00193
00194     typedef Tree::Const_iterator Const_iterator;
00195
00196     Const_iterator begin() const { return _tree.begin(); }
00197     Const_iterator end() const { return _tree.end(); }
00198
00199     Name_space(L4Re::Util::Dbg const &dbg, L4Re::Util::Err const &err)
00200     : _dbg(dbg), _err(err)
00201     {}
00202
00206     virtual ~Name_space() {}
00207
00208     Entry *find(Name const &name) const { return _tree.find_node(name); }
00209     Entry *remove(Name const &name) { return _tree.remove(name); }
00210     Entry *find_iter(Name const &pname) const
00211     {
00212         Name name = pname;
00213         _dbg.printf("resolve '%.s': ", name.len(), name.start());
00214         Name_space const *ns = this;
00215         while (ns)
00216         {
00217             cxx::String::Index sep = name.find("/");
00218             cxx::String part;
00219             if (!name.eof(sep))
00220                 part = name.head(sep);
00221             else
00222                 part = name;
00223
00224             _dbg.cprintf(" '%.s'", part.len(), part.start());
00225             Entry *o = ns->find(Name(part.start(), part.len()));
00226
00227             if (!o)
00228             {
00229                 _dbg.cprintf(": resolution failed: '%.s' remaining\n",
00230                             name.len(), name.start());
00231                 return 0;

```

```

00232     }
00233
00234     auto const *obj = o->obj()->obj();
00235     ns = dynamic_cast<Name_space const *>(obj);
00236     if (ns)
00237     {
00238         if (!name.eof(sep))
00239         {
00240             name = name.substr(sep + 1);
00241             continue;
00242         }
00243     }
00244
00245     _dbg.cprintf(": found object: %p (%s)\n",
00246                 obj, obj ? typeid(*obj).name() : "");
00247
00248     return o;
00249 }
00250
00251 return 0;
00252 }
00253
00254 bool insert(Entry *e) { return _tree.insert(e).second; }
00255
00256 void dump(bool rec = false, int indent = 0) const;
00257
00258 protected:
00259 // server support -----
00272 virtual Entry *alloc_dynamic_entry(Name const &n, unsigned flags) = 0;
00273
00279 virtual void free_dynamic_entry(Entry *e) = 0;
00280
00303 virtual l4_ret_t get_epiface(l4_umword_t data, bool is_local, L4::Epiface **lo) = 0;
00304
00317 virtual l4_ret_t copy_receive_cap(L4::Cap<void> *cap) = 0;
00318
00327 virtual void free_capability(L4::Cap<void> cap) = 0;
00328
00337 virtual void free_epiface(L4::Epiface *epiface) = 0;
00338
00339 l4_ret_t insert_entry(Name const &name, unsigned flags, Entry **e)
00340 {
00341     Entry *n = find(name);
00342     if (n && n->obj()->is_valid())
00343     {
00344         if (!(flags & L4Re::Namespace::Overwrite)
00345             && n->obj()->cap().validate(L4_BASE_TASK_CAP).label() > 0)
00346             return -L4_EEXIST;
00347
00348         if (n->obj()->is_local())
00349             free_epiface(n->obj()->obj());
00350         else
00351             free_capability(n->obj()->cap());
00352
00353         if (n->is_dynamic())
00354         {
00355             remove(n->name());
00356             free_dynamic_entry(n);
00357             n = 0;
00358         }
00359         else
00360         {
00361             if (!n->obj()->is_replacable())
00362                 return -L4_EEXIST;
00363             n->obj()->reset(Obj::F_rw);
00364         }
00365     }
00366
00367     flags &= L4Re::Namespace::Cap_flags;
00368     if (!n)
00369     {
00370         if (!(n = alloc_dynamic_entry(name, flags)))
00371             return -L4_ENOMEM;
00372         else
00373         {
00374             if (!insert(n))
00375             {
00376                 free_dynamic_entry(n);
00377                 return -L4_EEXIST;
00378             }
00379         }
00380     }
00381
00382     *e = n;
00383     return 0;
00384 }
00385

```

```

00386 public:
00387     // server interface -----
00388     L4_ret_t op_query(L4Re::Namespace::Rights,
00389                     L4::Ipc::Array_in_buf<char, unsigned long> const &name,
00390                     L4::Ipc::Snd_fpage &snd_cap, L4::Ipc::Opt<L4::Opcode> &dummy,
00391                     L4::Ipc::Opt<L4::Ipc::Array_ref<char, unsigned long> > &out_name)
00392     {
00393     #if 1
00394         _dbg.printf("query: [%ld] '%.*s'\n", name.length,
00395                     static_cast<int>(name.length), name.data);
00396     #endif
00397
00398         char const *sep
00399             = static_cast<char const*>(memchr(name.data, '/', name.length));
00400         unsigned long part;
00401         if (sep)
00402             part = sep - name.data;
00403         else
00404             part = name.length;
00405
00406         Entry *n = find(Name(name.data, part));
00407         if (!n)
00408             return -L4_ENOENT;
00409         else if (!n->obj()->is_valid())
00410             return -L4_EAGAIN;
00411         else
00412         {
00413             if (n->obj()->cap().validate(L4_BASE_TASK_CAP).label() <= 0)
00414             {
00415                 if (n->obj()->is_local())
00416                     free_epiface(n->obj()->obj());
00417                 else
00418                     free_capability(n->obj()->cap());
00419
00420                 if (n->is_dynamic())
00421                 {
00422                     remove(n->name());
00423                     free_dynamic_entry(n);
00424                 }
00425                 return -L4_ENOENT;
00426             }
00427
00428             // make picky clients happy
00429             dummy.set_valid();
00430             // prevent warning about writing uninitialized data in IPC framework
00431             dummy = 0;
00432
00433             L4_ret_t result = 0;
00434
00435             out_name.set_valid();
00436             if (part < name.length)
00437             {
00438                 result |= L4Re::Namespace::Partly_resolved;
00439                 memcpy(out_name->data, name.data + part + 1, name.length - part - 1);
00440                 out_name->length = name.length - part - 1;
00441             }
00442             else
00443                 out_name->length = 0;
00444
00445             unsigned flags = L4_CAP_FPAGE_R;
00446             if (n->obj()->is_rw()) flags |= L4_CAP_FPAGE_W;
00447             if (n->obj()->is_strong()) flags |= L4_CAP_FPAGE_S;
00448
00449             snd_cap = L4::Ipc::Snd_fpage(n->obj()->cap(), flags);
00450             _dbg.printf(" result = %x flgs=%x strg=%d\n",
00451                         result, flags, static_cast<int>(n->obj()->is_strong()));
00452             return result;
00453         }
00454     }
00455
00456     L4_ret_t op_register_obj(L4Re::Namespace::Rights, unsigned flags,
00457                             L4::Ipc::Array_in_buf<char, unsigned long> const &name,
00458                             L4::Ipc::Snd_fpage &cap)
00459     {
00460         if (name.length == 0 || memchr(name.data, '/', name.length))
00461             return -L4_EINVAL;
00462
00463         L4::Cap<void> reg_cap(L4_INVALID_CAP);
00464         L4::Epiface *src_o = 0;
00465
00466         // Did we receive something we have handed out ourselves? If yes,
00467         // register the object under the given name but do not allocate
00468         // anything more.
00469         if (cap.id_received() || cap.local_id_received())
00470         {
00471             if (L4_ret_t ret = get_epiface(cap.data(), cap.local_id_received(), &src_o))
00472                 return ret;

```

```

00473
00474     // Make sure rights are restricted to the mapped rights.
00475     flags &= (cap.data() & 0x3UL) | ~0x3UL;
00476 }
00477 else if (cap.cap_received())
00478 {
00479     if (l4_ret_t ret = copy_receive_cap(&reg_cap))
00480         return ret;
00481 }
00482 else if (!cap.is_valid())
00483 {
00484     reg_cap = L4::Cap<void>::Invalid;
00485 }
00486 else
00487     return -L4_EINVAL;
00488
00489 // got a valid entry to register
00490 _dbg.printf("register: '%.*s' flags=%x\n", static_cast<int>(name.length),
00491             name.data, flags);
00492
00493 Name _name(name.data, name.length);
00494
00495 Entry *n;
00496 if (l4_ret_t r = insert_entry(_name, flags, &n))
00497 {
00498     if (cap.cap_received())
00499         free_capability(reg_cap);
00500     if (src_o)
00501         free_epiface(src_o);
00502
00503     return r;
00504 }
00505
00506 if (src_o)
00507     n->set(Names::Obj(flags & L4Re::Namespace::Cap_flags, src_o));
00508 else if (reg_cap.is_valid())
00509     n->set(Names::Obj(flags & L4Re::Namespace::Cap_flags, reg_cap));
00510
00511 return 0;
00512 }
00513
00514 l4_ret_t op_unlink(L4Re::Namespace::Rights,
00515                  L4::Ipcc::Array_in_buf<char, unsigned long> const &name)
00516 {
00517     #if 1
00518     _dbg.printf("unlink: [%ld] '%.*s'\n", name.length,
00519                static_cast<int>(name.length), name.data);
00520     #endif
00521
00522     char const *sep
00523         = static_cast<char const*>(memchr(name.data, '/', name.length));
00524     unsigned long part;
00525     if (sep)
00526         part = sep - name.data;
00527     else
00528         part = name.length;
00529
00530     Entry *n = find(Name(name.data, part));
00531     if (!n || !n->obj()->is_valid())
00532         return -L4_ENOENT;
00533
00534     if (n->obj()->is_local())
00535         free_epiface(n->obj()->obj());
00536     else
00537         free_capability(n->obj()->cap());
00538
00539     if (n->is_dynamic())
00540     {
00541         remove(n->name());
00542         free_dynamic_entry(n);
00543     }
00544     else
00545         return -L4_EACCESS;
00546
00547     return 0;
00548 }
00549 };
00550 };
00551 }}}
00552 }}}
00553

```

## 16.396 object\_registry

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00002 /*
00003  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00004  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00005  *      economic rights: Technische Universität Dresden (Germany)
00006  *
00007  * License: see LICENSE.spdx (in this directory or the directories above)
00008  */
00009
00010 #pragma once
00011
00012 #include <l4/re/util/cap_alloc>
00013 #include <l4/re/util/unique_cap>
00014 #include <l4/re/consts>
00015 #include <l4/re/env>
00016
00017 #include <l4/sys/cxx/ipc_server_loop>
00018 #include <l4/sys/factory>
00019 #include <l4/sys/task>
00020 #include <l4/sys/thread>
00021 #include <l4/sys/ipc_gate>
00022
00023 #include <l4/cxx/exceptions>
00024
00025 namespace L4Re { namespace Util {
00026
00041 class Object_registry :
00042     public L4::Basic_registry,
00043     public L4::Registry_iface
00044 {
00049     struct Null_handler : L4::Epiface_t<Null_handler, L4::Kobject>
00050     {};
00051
00052 protected:
00053     L4::Cap<L4::Thread> _server;
00054     L4::Cap<L4::Factory> _factory;
00055     L4::Ipc_svr::Server_iface *_sif;
00056
00057 private:
00058     Null_handler _null_handler;
00059
00060 public:
00066     explicit
00067     Object_registry(L4::Ipc_svr::Server_iface *sif)
00068     : _server(L4Re::Env::env()->main_thread()),
00069       _factory(L4Re::Env::env()->factory()),
00070       _sif(sif)
00071     {}
00072
00081     Object_registry(L4::Ipc_svr::Server_iface *sif,
00082                     L4::Cap<L4::Thread> server,
00083                     L4::Cap<L4::Factory> factory)
00084     : _server(server), _factory(factory), _sif(sif)
00085     {}
00086
00087 private:
00088     typedef L4::Ipc_svr::Server_iface Server_iface;
00089     typedef Server_iface::Demand Demand;
00090
00091     L4::Cap<L4::Rcv_endpoint>
00092     _register_ep(L4::Epiface *o, L4::Cap<L4::Rcv_endpoint> ep,
00093                 Demand const &demand)
00094     {
00095         int err = _sif->alloc_buffer_demand(demand);
00096         if (err < 0)
00097             return L4::Cap<L4::Rcv_endpoint>(err | L4_INVALID_CAP_BIT);
00098
00099         err = o->set_server(_sif, ep);
00100         if (err < 0)
00101             return L4::Cap<L4::Rcv_endpoint>(err | L4_INVALID_CAP_BIT);
00102
00103         l4_umword_t id = l4_umword_t(o);
00104         err = l4_error(ep->bind_thread(_server, id));
00105         if (err < 0)
00106             return L4::Cap<L4::Rcv_endpoint>(err | L4_INVALID_CAP_BIT);
00107
00108         return ep;
00109     }
00110
00111     L4::Cap<void> _register_ep(L4::Epiface *o, char const *service,
00112                               Demand const &demand)
00113     {
00114         L4::Cap<L4::Rcv_endpoint> cap = L4Re::Env::env()->get_cap<L4::Rcv_endpoint>(service);
00115         if (!cap.is_valid())

```

```

00116         return cap;
00117
00118     return _register_ep(o, cap, demand);
00119 }
00120
00121 L4::Cap<void> _register_gate(L4::Epiface *o, Demand const &demand)
00122 {
00123     int err = _sif->alloc_buffer_demand(demand);
00124     if (err < 0)
00125         return L4::Cap<void>(err | L4_INVALID_CAP_BIT);
00126
00127     auto cap = L4Re::Util::make_unique_cap<L4::Kobject>();
00128
00129     if (!cap.is_valid())
00130         return cap.get();
00131
00132     l4_umword_t id = l4_umword_t(o);
00133     err = l4_error(_factory->create_gate(cap.get(), _server, id));
00134     if (err < 0)
00135         return L4::Cap<void>(err | L4_INVALID_CAP_BIT);
00136
00137     err = o->set_server(_sif, cap.get(), true);
00138     if (err < 0)
00139         return L4::Cap<void>(err | L4_INVALID_CAP_BIT);
00140
00141     return cap.release();
00142 }
00143
00144 L4::Cap<L4::Irq> _register_irq(L4::Epiface *o,
00145                               Demand const &demand)
00146 {
00147     int err = _sif->alloc_buffer_demand(demand);
00148     if (err < 0)
00149         return L4::Cap<L4::Irq>(err | L4_INVALID_CAP_BIT);
00150
00151     auto cap = L4Re::Util::make_unique_cap<L4::Irq>();
00152
00153     if (!cap.is_valid())
00154         return cap.get();
00155
00156     l4_umword_t id = l4_umword_t(o);
00157     err = l4_error(_factory->create(cap.get()));
00158     if (err < 0)
00159         return L4::Cap<L4::Irq>(err | L4_INVALID_CAP_BIT);
00160
00161     err = o->set_server(_sif, cap.get(), true);
00162     if (err < 0)
00163         return L4::Cap<L4::Irq>(err | L4_INVALID_CAP_BIT);
00164
00165     err = l4_error(cap->bind_thread(_server, id));
00166     if (err < 0)
00167         return L4::Cap<L4::Irq>(err | L4_INVALID_CAP_BIT);
00168
00169     return cap.release();
00170 }
00171
00172 static Demand _get_buffer_demand(L4::Epiface *o)
00173 { return o->get_buffer_demand(); }
00174
00175 template<typename T>
00176 static Demand _get_buffer_demand(T *,
00177     typename L4::Kobject_typeid<typename T::Interface>::Demand
00178     d = typename L4::Kobject_typeid<typename T::Interface>::Demand())
00179 { return d; }
00180
00181 public:
00194 L4::Cap<void> register_obj(L4::Epiface *o, char const *service) override
00195 {
00196     return _register_ep(o, service, _get_buffer_demand(o));
00197 }
00198
00211 L4::Cap<void> register_obj(L4::Epiface *o) override
00212 {
00213     return _register_gate(o, _get_buffer_demand(o));
00214 }
00215
00227 L4::Cap<L4::Irq> register_irq_obj(L4::Epiface *o) override
00228 {
00229     return _register_irq(o, _get_buffer_demand(o));
00230 }
00231
00245 L4::Cap<L4::Rcv_endpoint>
00246 register_obj(L4::Epiface *o, L4::Cap<L4::Rcv_endpoint> ep) override
00247 {
00248     return _register_ep(o, ep, _get_buffer_demand(o));
00249 }
00250

```

```

00251
00262 void unregister_obj(L4::Epiface *o, bool unmap = true) override
00263 {
00264     L4::Epiface::Stored_cap c;
00265
00266     if (!o || !o->obj_cap().is_valid())
00267         return;
00268
00269     c = o->obj_cap();
00270
00271     if (unmap)
00272         L4::Cap<L4::Task>(L4Re::This_task)->unmap(c.fpage(), L4_FP_ALL_SPACES);
00273
00274     // make sure unhandled ipc ends up with the null handler
00275     L4::Thread::Modify_senders todo;
00276     todo.add(~3UL, reinterpret_cast<l4_umword_t>(o),
00277             ~0UL, reinterpret_cast<l4_umword_t>
00278                 (static_cast<L4::Epiface *>(&_null_handler)));
00279     _server->modify_senders(todo);
00280
00281     // we use bit 4 to indicated an internally allocated cap
00282     if (c.managed())
00283         cap_alloc.free(c);
00284
00285     o->set_server(0, L4::Cap<void>::Invalid);
00286 }
00287 };
00288
00292 template< typename LOOP_HOOKS = L4::Ipc_svr::Default_loop_hooks >
00293 class Registry_server : public L4::Server<LOOP_HOOKS>
00294 {
00295 private:
00296     typedef L4::Server<LOOP_HOOKS> Base;
00297     Object_registry _registry;
00298
00299 public:
00305 Registry_server() : _registry(this)
00306 {}
00307
00317 Registry_server(l4_utcb_t *, L4::Cap<L4::Thread> server,
00318                 L4::Cap<L4::Factory> factory) L4_DEPRECATED("Omit UTCB pointer argument")
00319 : _registry(this, server, factory)
00320 {}
00321
00328 Registry_server(L4::Cap<L4::Thread> server,
00329                 L4::Cap<L4::Factory> factory)
00330 : _registry(this, server, factory)
00331 {}
00332
00334 Object_registry const *registry() const { return &_registry; }
00336 Object_registry *registry() { return &_registry; }
00337
00344 void L4_NORETURN loop(l4_utcb_t *utcb = l4_utcb())
00345 { Base::template loop<L4::Runtime_error, Object_registry &>(_registry, utcb); }
00346
00355 template <typename Printer>
00356 void L4_NORETURN loop_dbg(Printer printer, l4_utcb_t *utcb = l4_utcb())
00357 {
00358     Base::template loop_dbg<L4::Runtime_error, Object_registry &, Printer>
00359         (_registry, printer, utcb);
00360 }
00361 };
00362 }

```

## 16.397 poll\_timeout\_kipclock


```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00002 /*
00003  * (c) 2012 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00004  *     economic rights: Technische Universität Dresden (Germany)
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007 #pragma once
00008
00009 #include <l4/sys/kip.h>
00010 #include <l4/re/env.h>
00011
00012 namespace L4 {
00013
00035 class Poll_timeout_kipclock
00036 {
00037 public:
00042 Poll_timeout_kipclock(unsigned poll_time_us)

```


### 16.398 I4/re/util/region\_mapping File Reference

```
#include <l4/cxx/avl_map>
#include <l4/sys/types.h>
#include <l4/re/rm>
Include dependency graph for region_mapping:
```





This graph shows which files directly or indirectly include this file:



### Namespaces

- namespace [L4Re](#)  
*[L4Re](#) C++ Interfaces.*
- namespace [L4Re::Util](#)  
*Documentation of the [L4](#) Runtime Environment utility functionality in C++.*

## 16.398.1 Detailed Description

Region handling.

Definition in file [region\\_mapping](#).

## 16.399 region\_mapping

[Go to the documentation of this file.](#)

```

00001 // -*- Mode: C++ -*-
00002 // vim:ft=cpp
00007 /*
00008  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00009  *               Alexander Warg <warg@os.inf.tu-dresden.de>,
00010  *               Björn Döbel <doebel@os.inf.tu-dresden.de>
00011  *               economic rights: Technische Universität Dresden (Germany)
00012  *
00013  * License: see LICENSE.spdx (in this directory or the directories above)
00014  */
00015
00016 #pragma once
00017
00018 #include <l4/cxx/avl_map>
00019 #include <l4/sys/types.h>
00020 #include <l4/re/rm>
00021
00022 namespace L4Re { namespace Util {
00023
00024   class Region
00025   {
00026   private:
00027     l4_addr_t _start, _end;
00028     #ifdef CONFIG_L4RE_REGION_INFO
00029     char _dbg_name[40]; // Not a 0-terminating string
00030     unsigned char _dbg_name_len = 0;
00031     static_assert(sizeof(_dbg_name) < 256);
00032     Rm::Offset _dbg_backing_offset = 0;

```

```

00033 #endif
00034
00035 public:
00036     Region() noexcept : _start(~0UL), _end(~0UL) {}
00037     Region(l4_addr_t addr) noexcept : _start(addr), _end(addr) {}
00038     Region(l4_addr_t start, l4_addr_t end) noexcept
00039         : _start(start), _end(end) {}
00040     Region(l4_addr_t start, l4_addr_t end,
00041           char const *name, unsigned name_len,
00042           Rm::Offset backing_offset) noexcept
00043         : _start(start), _end(end)
00044     {
00045 #ifdef CONFIG_L4RE_REGION_INFO
00046         _dbg_name_len = name_len > sizeof(_dbg_name)
00047             ? sizeof(_dbg_name) : name_len;
00048         for (unsigned i = 0; i < _dbg_name_len; ++i)
00049             _dbg_name[i] = name[i];
00050
00051         _dbg_backing_offset = backing_offset;
00052 #else
00053         (void)name;
00054         (void)name_len;
00055         (void)backing_offset;
00056 #endif
00057     }
00058     l4_addr_t start() const noexcept { return _start; }
00059     l4_addr_t end() const noexcept { return _end; }
00060     unsigned long size() const noexcept { return end() - start() + 1; }
00061     bool invalid() const noexcept { return _start == ~0UL && _end == ~0UL; }
00062     bool operator < (Region const &o) const noexcept
00063     { return end() < o.start(); }
00064     bool contains(Region const &o) const noexcept
00065     { return o.start() >= start() && o.end() <= end(); }
00066     bool operator == (Region const &o) const noexcept
00067     { return o.start() == start() && o.end() == end(); }
00068     ~Region() noexcept {}
00069
00070 #ifdef CONFIG_L4RE_REGION_INFO
00071     char const *name() const { return _dbg_name; }
00072     unsigned char name_len() const { return _dbg_name_len; }
00073     Rm::Offset backing_offset() const { return _dbg_backing_offset; }
00074 #else
00075     char const *name() const { return "N/A"; }
00076     unsigned char name_len() const { return 3; }
00077     Rm::Offset backing_offset() const { return 0; }
00078 #endif
00079 };
00080
00081 template<typename DS, typename OPS>
00082 class Region_handler
00083 {
00084 private:
00085     L4Re::Rm::Offset _offs;
00086     DS _mem;
00087     l4_cap_idx_t _client_cap = L4_INVALID_CAP;
00088     L4Re::Rm::Region_flags _flags;
00089
00090 public:
00091     typedef DS Dataspace;
00092     typedef OPS Ops;
00093     typedef typename OPS::Map_result Map_result;
00094
00095     Region_handler() noexcept : _offs(0), _mem(), _flags() {}
00096
00097     Region_handler(Dataspace const &mem, l4_cap_idx_t client_cap,
00098                   L4Re::Rm::Offset offset = 0,
00099                   L4Re::Rm::Region_flags flags = L4Re::Rm::Region_flags(0)) noexcept
00100         : _offs(offset), _mem(mem), _client_cap(client_cap), _flags(flags)
00101     {}
00102
00103     Dataspace const &memory() const noexcept
00104     { return _mem; }
00105
00106     l4_cap_idx_t client_cap_idx() const noexcept
00107     { return _client_cap; }
00108
00109     L4Re::Rm::Offset offset() const noexcept
00110     { return _offs; }
00111
00112     constexpr bool is_ro() const noexcept
00113     { return !(_flags & L4Re::Rm::F::W); }
00114
00115     L4Re::Rm::Region_flags caching() const noexcept
00116     { return _flags & L4Re::Rm::F::Caching_mask; }
00117
00118     L4Re::Rm::Region_flags flags() const noexcept
00119     { return _flags; }

```

```

00120
00121 Region_handler operator + (l4_int64_t offset) const noexcept
00122 { Region_handler n = *this; n._offs += offset; return n; }
00123
00124 void free(l4_addr_t start, unsigned long size) const noexcept
00125 { Ops::free(this, start, size); }
00126
00127 int map(l4_addr_t addr, Region const &r, bool writable,
00128         Map_result *result) const
00129 { return Ops::map(this, addr, r, writable, result); }
00130
00131 int map_info(l4_addr_t *start_addr, l4_addr_t *end_addr) const
00132 { return Ops::map_info(this, start_addr, end_addr); }
00133 };
00134
00135 template<typename Hdlr, template<typename T> class Alloc>
00136 class Region_map
00137 {
00138 protected:
00139     typedef cxx::Avl_map<Region, Hdlr, cxx::Lt_functor, Alloc> Tree;
00140
00141     Tree _rm;
00142     Tree _am;
00143
00144 private:
00145     l4_addr_t _start;
00146     l4_addr_t _end;
00147
00148 protected:
00149     void set_limits(l4_addr_t start, l4_addr_t end) noexcept
00150     {
00151         _start = start;
00152         _end = end;
00153     }
00154
00155 public:
00156     typedef typename Tree::Item_type Item;
00157     typedef typename Tree::Node Node;
00158     typedef typename Tree::Key_type Key_type;
00159     typedef Hdlr Region_handler;
00160
00161     typedef typename Tree::Iterator Iterator;
00162     typedef typename Tree::Const_iterator Const_iterator;
00163     typedef typename Tree::Rev_iterator Rev_iterator;
00164     typedef typename Tree::Const_rev_iterator Const_rev_iterator;
00165
00166     Iterator begin() noexcept { return _rm.begin(); }
00167     Const_iterator begin() const noexcept { return _rm.begin(); }
00168     Iterator end() noexcept { return _rm.end(); }
00169     Const_iterator end() const noexcept { return _rm.end(); }
00170
00171     Iterator area_begin() noexcept { return _am.begin(); }
00172     Const_iterator area_begin() const noexcept { return _am.begin(); }
00173     Iterator area_end() noexcept { return _am.end(); }
00174     Const_iterator area_end() const noexcept { return _am.end(); }
00175     Node area_find(Key_type const &c) const noexcept { return _am.find_node(c); }
00176
00177     l4_addr_t min_addr() const noexcept { return _start; }
00178     l4_addr_t max_addr() const noexcept { return _end; }
00179
00180     Region_map(l4_addr_t start, l4_addr_t end) noexcept : _start(start), _end(end) {}
00181
00182     Node find(Key_type const &key) const noexcept
00183     {
00184         Node n = _rm.find_node(key);
00185         if (!n)
00186             return Node();
00187
00188         // 'find' should find any region overlapping with the searched one, the
00189         // caller should check for further requirements
00190         if (0)
00191             if (!n->first.contains(key))
00192                 return Node();
00193
00194         return n;
00195     }
00196
00197     Node lower_bound(Key_type const &key) const noexcept
00198     {
00199         Node n = _rm.lower_bound_node(key);
00200         return n;
00201     }
00202
00203     Node lower_bound_area(Key_type const &key) const noexcept
00204     {
00205         Node n = _am.lower_bound_node(key);
00206         return n;

```

```

00207     }
00208
00209     l4_addr_t attach_area(l4_addr_t addr, unsigned long size,
00210                          L4Re::Rm::Flags flags = L4Re::Rm::Flags(0),
00211                          unsigned char align = L4_PAGESHIFT) noexcept
00212     {
00213         if (size < 2)
00214             return L4_INVALID_ADDR;
00215
00216         Region c;
00217
00218         if (!(flags & L4Re::Rm::F::Search_addr))
00219         {
00220             c = Region(addr, addr + size - 1);
00221             Node r = _am.find_node(c);
00222             if (r)
00223                 return L4_INVALID_ADDR;
00224         }
00225
00226         while (flags & L4Re::Rm::F::Search_addr)
00227         {
00228             if (addr < min_addr() || (addr + size - 1) > max_addr())
00229                 addr = min_addr();
00230
00231             addr = find_free(addr, max_addr(), size, align, flags);
00232             if (addr == L4_INVALID_ADDR)
00233                 return L4_INVALID_ADDR;
00234
00235             c = Region(addr, addr + size - 1);
00236             Node r = _am.find_node(c);
00237             if (!r)
00238                 break;
00239
00240             if (r->first.end() >= max_addr())
00241                 return L4_INVALID_ADDR;
00242
00243             addr = r->first.end() + 1;
00244         }
00245
00246         if (_am.insert(c, Hdlr(typename Hdlr::Dataspace(), 0, 0, flags.region_flags())).second == 0)
00247             return addr;
00248
00249         return L4_INVALID_ADDR;
00250     }
00251
00252     bool detach_area(l4_addr_t addr) noexcept
00253     {
00254         if (_am.remove(addr))
00255             return false;
00256
00257         return true;
00258     }
00259
00260     void *attach(void *addr, unsigned long size, Hdlr const &hdlr,
00261                 L4Re::Rm::Flags attach_flags = L4Re::Rm::Flags(0),
00262                 unsigned char align = L4_PAGESHIFT,
00263                 char const *name = nullptr, unsigned name_len = 0,
00264                 L4Re::Rm::Offset backing_offset = 0) noexcept
00265     {
00266         if (size < 2)
00267             return L4_INVALID_PTR;
00268
00269         l4_addr_t beg, end;
00270         int err = hdlr.map_info(&beg, &end);
00271         if (err > 0)
00272         {
00273             // Mapping address determined by underlying dataspace. Make sure we
00274             // prevent any additional alignment. We already know the place!
00275             beg += hdlr.offset();
00276             end = beg + size - 1U;
00277             align = L4_PAGESHIFT;
00278
00279             // In case of exact mappings, the supplied address must match because
00280             // we cannot remap.
00281             if (!(attach_flags & L4Re::Rm::F::Search_addr)
00282                 && reinterpret_cast<l4_addr_t>(addr) != beg)
00283                 return L4_INVALID_PTR;
00284
00285             // When searching for a suitable address, the start must cover the
00286             // dataspace beginning to "find" the right spot.
00287             if ((attach_flags & L4Re::Rm::F::Search_addr)
00288                 && reinterpret_cast<l4_addr_t>(addr) > beg)
00289                 return L4_INVALID_PTR;
00290         }
00291         else if (err == 0)
00292         {
00293             beg = reinterpret_cast<l4_addr_t>(addr);

```

```

00294         end = max_addr();
00295     }
00296     else if (err < 0)
00297         return L4_INVALID_PTR;
00298
00299     if (attach_flags & L4Re::Rm::F::In_area)
00300     {
00301         Node r = _am.find_node(Region(beg, beg + size - 1));
00302         if (!r || (r->second.flags() & L4Re::Rm::F::Reserved))
00303             return L4_INVALID_PTR;
00304
00305         end = r->first.end();
00306     }
00307
00308     if (attach_flags & L4Re::Rm::F::Search_addr)
00309     {
00310         beg = find_free(beg, end, size, align, attach_flags);
00311         if (beg == L4_INVALID_ADDR)
00312             return L4_INVALID_PTR;
00313     }
00314
00315     if (!(attach_flags & (L4Re::Rm::F::Search_addr | L4Re::Rm::F::In_area))
00316         && _am.find_node(Region(beg, beg + size - 1)))
00317         return L4_INVALID_PTR;
00318
00319     if (beg < min_addr() || beg + size - 1 > end)
00320         return L4_INVALID_PTR;
00321
00322     if (_rm.insert(Region(beg, beg + size - 1,
00323                          name, name_len, backing_offset), hdlr).second
00324         == 0)
00325         return reinterpret_cast<void*>(beg);
00326
00327     return L4_INVALID_PTR;
00328 }
00329
00330 int detach(void *addr, unsigned long sz, unsigned flags,
00331            Region *reg, Hdlr *hdlr) noexcept
00332 {
00333     l4_addr_t a = reinterpret_cast<l4_addr_t>(addr);
00334     Region dr(a, a + sz - 1);
00335     Region res(~0UL, 0);
00336
00337     Node r = find(dr);
00338     if (!r)
00339         return -L4_ENOENT;
00340
00341     Region g = r->first;
00342     Hdlr const &h = r->second;
00343
00344     if (flags & L4Re::Rm::Detach_overlap || dr.contains(g))
00345     {
00346         // Successful removal of the AVL tree item also frees the node.
00347         Hdlr h_copy = h;
00348
00349         if (_rm.remove(g))
00350             return -L4_ENOENT;
00351
00352         if (!(flags & L4Re::Rm::Detach_keep) && (h_copy.flags() & L4Re::Rm::F::Detach_free))
00353             h_copy.free(0, g.size());
00354
00355         if (hdlr)
00356             *hdlr = h_copy;
00357         if (reg)
00358             *reg = g;
00359
00360         if (find(dr))
00361             return Rm::Detached_ds | Rm::Detach_again;
00362         else
00363             return Rm::Detached_ds;
00364     }
00365     else if (dr.start() <= g.start())
00366     {
00367         // Move the start of a region.
00368
00369         if (!(flags & L4Re::Rm::Detach_keep) && (h.flags() & L4Re::Rm::F::Detach_free))
00370             h.free(0, dr.end() + 1 - g.start());
00371
00372         unsigned long sz = dr.end() + 1 - g.start();
00373         Item &cn = const_cast<Item &>(*r);
00374         cn.first = Region(dr.end() + 1, g.end(), g.name(), g.name_len(),
00375                          g.backing_offset() + sz);
00376         cn.second = cn.second + sz;
00377         if (hdlr)
00378             *hdlr = Hdlr();
00379         if (reg)
00380             *reg = Region(g.start(), dr.end());

```

```

00381         if (find(dr))
00382             return Rm::Kept_ds | Rm::Detach_again;
00383         else
00384             return Rm::Kept_ds;
00385     }
00386     else if (dr.end() >= g.end())
00387     {
00388         // Move the end of a region.
00389
00390         if (!(flags & L4Re::Rm::Detach_keep)
00391             && (h.flags() & L4Re::Rm::F::Detach_free))
00392             h.free(dr.start() - g.start(), g.end() + 1 - dr.start());
00393
00394         Item &cn = const_cast<Item &>(*r);
00395         cn.first = Region(g.start(), dr.start() - 1, g.name(), g.name_len(),
00396                         g.backing_offset());
00397         if (hdlr)
00398             *hdlr = Hdlr();
00399         if (reg)
00400             *reg = Region(dr.start(), g.end());
00401
00402         if (find(dr))
00403             return Rm::Kept_ds | Rm::Detach_again;
00404         else
00405             return Rm::Kept_ds;
00406     }
00407     else if (g.contains(dr))
00408     {
00409         // Split a single region that contains the new region.
00410
00411         if (!(flags & L4Re::Rm::Detach_keep) && (h.flags() & L4Re::Rm::F::Detach_free))
00412             h.free(dr.start() - g.start(), dr.size());
00413
00414         // First move the end off the existing region before the new one.
00415         Item &cn = const_cast<Item &>(*r);
00416         cn.first = Region(g.start(), dr.start()-1, g.name(), g.name_len(),
00417                         g.backing_offset());
00418
00419         int err;
00420
00421         // Insert a second region for the remaining tail of
00422         // the old existing region.
00423         auto tail_sz = dr.end() + 1 - g.start();
00424         err = _rm.insert(Region(dr.end() + 1, g.end(), g.name(), g.name_len(),
00425                               g.backing_offset() + tail_sz),
00426                        h + tail_sz).second;
00427
00428         if (err)
00429             return err;
00430
00431         if (hdlr)
00432             *hdlr = h;
00433         if (reg)
00434             *reg = dr;
00435         return Rm::Split_ds;
00436     }
00437
00438     return -L4_ENOENT;
00439 }
00440
00441 l4_addr_t find_free(l4_addr_t start, l4_addr_t end, l4_addr_t size,
00442                    unsigned char align, L4Re::Rm::Flags attach_flags) const noexcept;
00443 };
00444
00445 template<typename Hdlr, template<typename T> class Alloc>
00446 l4_addr_t
00447 Region_map<Hdlr, Alloc>::find_free(l4_addr_t start, l4_addr_t end,
00448                                   unsigned long size, unsigned char align, L4Re::Rm::Flags attach_flags) const noexcept
00449 {
00450     l4_addr_t addr = start;
00451
00452     if (addr == ~0UL || addr < min_addr() || addr >= end)
00453         addr = min_addr();
00454
00455     addr = l4_round_size(addr, align);
00456     Node r;
00457
00458     for (;;)
00459     {
00460         if (addr > 0 && addr - 1 > end - size)
00461             return L4_INVALID_ADDR;
00462
00463         Region c(addr, addr + size - 1);
00464         r = _rm.find_node(c);
00465
00466         if (!r)
00467             {

```

```

00468         if (!(attach_flags & L4Re::Rm::F::In_area) && (r = _am.find_node(c)))
00469         {
00470             if (r->first.end() > end - size)
00471                 return L4_INVALID_ADDR;
00472
00473             addr = l4_round_size(r->first.end() + 1, align);
00474             continue;
00475         }
00476
00477         break;
00478     }
00479     else if (r->first.end() > end - size)
00480         return L4_INVALID_ADDR;
00481
00482     addr = l4_round_size(r->first.end() + 1, align);
00483 }
00484
00485 if (!r)
00486     return addr;
00487
00488 return L4_INVALID_ADDR;
00489 }
00490
00491 }

```

## 16.400 region\_mapping\_svr

```

00001 // vi:set ft=c++: -- Mode: C++ --
00002 /*
00003  * (c) 2014 Alexander Warg <alexander.warg@kernkonzept.com>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007 #pragma once
00008
00009 #include <l4/sys/types.h>
00010 #include <l4/re/rm>
00011 #include <l4/re/util/region_mapping>
00012
00013 namespace L4Re { namespace Util {
00014
00015     template<typename DERIVED, typename Dbg>
00016     struct Rm_server
00017     {
00018     private:
00019         DERIVED *rm() { return static_cast<DERIVED*>(this); }
00020         DERIVED const *rm() const { return static_cast<DERIVED const*>(this); }
00021     public:
00022
00023         l4_ret_t op_attach(L4Re::Rm::Rights, l4_addr_t &_start,
00024                             unsigned long size, Rm::Flags flags,
00025                             L4::Ipc::Snd_fpage ds_cap, L4Re::Rm::Offset offs,
00026                             unsigned char align, l4_cap_idx_t client_cap_idx,
00027                             L4::Ipc::String<> name, L4Re::Rm::Offset backing_offset)
00028         {
00029             typename DERIVED::Dataspace ds;
00030
00031             if (!(flags & (Rm::F::Reserved | Rm::F::Kernel)))
00032             {
00033                 if (long r = rm()->validate_ds
00034                     (static_cast<DERIVED*>(this)->server_iface(), ds_cap,
00035                      flags.region_flags(), &ds))
00036                     return r;
00037             }
00038
00039             size = l4_round_page(size);
00040             l4_addr_t start = l4_trunc_page(_start);
00041
00042             if (size < L4_PAGESIZE)
00043                 return -L4_EINVAL;
00044
00045             Rm::Region_flags r_flags = flags.region_flags();
00046             Rm::Attach_flags a_flags = flags.attach_flags();
00047
00048             typename DERIVED::Region_handler handler(ds, client_cap_idx, offs, r_flags);
00049             start = l4_addr_t(rm()->attach(reinterpret_cast<void*>(start), size,
00050                                     handler, a_flags, align,
00051                                     name.data,
00052                                     // L4::Ipc::String includes terminating '\0'
00053                                     name.length ? name.length - 1 : 0,
00054                                     backing_offset));
00055         }
00056     };
00057 }

```

```

00065     if (start == L4_INVALID_ADDR)
00066         return -L4_EADDRNOTAVAIL;
00067
00068     _start = start;
00069     return L4_EOK;
00070 }
00071
00072 l4_ret_t op_free_area(L4Re::Rm::Rights, l4_addr_t start)
00073 {
00074     if (!rm()->detach_area(start))
00075         return -L4_ENOENT;
00076
00077     return L4_EOK;
00078 }
00079
00080 l4_ret_t op_find(L4Re::Rm::Rights, l4_addr_t &addr, unsigned long &size,
00081                 L4Re::Rm::Flags &flags, L4Re::Rm::Offset &offset,
00082                 L4::Cap<L4Re::Dataspace> &m)
00083 {
00084     if (!DERIVED::Have_find)
00085         return -L4_EPERM;
00086
00087     Rm::Flags flag_area { 0 };
00088
00089     typename DERIVED::Node r = rm()->find(Region(addr, addr + size - 1));
00090     if (!r)
00091     {
00092         r = rm()->area_find(Region(addr, addr + size - 1));
00093         if (!r)
00094             return -L4_ENOENT;
00095         flag_area = Rm::F::In_area;
00096     }
00097
00098     addr = r->first.start();
00099     size = r->first.end() + 1 - addr;
00100
00101     flags = r->second.flags() | flag_area;
00102     offset = r->second.offset();
00103     m = L4::Cap<L4Re::Dataspace>(DERIVED::find_res(r->second.memory()));
00104     return L4_EOK;
00105 }
00106
00107 l4_ret_t op_detach(L4Re::Rm::Rights, l4_addr_t addr,
00108                  unsigned long size, unsigned flags,
00109                  l4_addr_t &start, l4_addr_t &rsz,
00110                  l4_cap_idx_t &mem_cap)
00111 {
00112     Region r;
00113     typename DERIVED::Region_handler h;
00114     int err = rm()->detach(reinterpret_cast<void*>(addr), size, flags, &r, &h);
00115     if (err < 0)
00116     {
00117         start = rsz = 0;
00118         mem_cap = L4_INVALID_CAP;
00119         return err;
00120     }
00121
00122     if (r.invalid())
00123     {
00124         start = rsz = 0;
00125         mem_cap = L4_INVALID_CAP;
00126         return -L4_ENOENT;
00127     }
00128
00129     start = r.start();
00130     rsz = r.size();
00131     mem_cap = h.client_cap_idx();
00132     return err;
00133 }
00134
00135 l4_ret_t op_reserve_area(L4Re::Rm::Rights, l4_addr_t &start, unsigned long size,
00136                        L4Re::Rm::Flags flags, unsigned char align)
00137 {
00138     start = rm()->attach_area(start, size, flags, align);
00139     if (start == L4_INVALID_ADDR)
00140         return -L4_EADDRNOTAVAIL;
00141     return L4_EOK;
00142 }
00143
00144 l4_ret_t op_get_regions(L4Re::Rm::Rights, l4_addr_t addr,
00145                       L4::Ipc::Ret_array<L4Re::Rm::Region> regions)
00146 {
00147     typename DERIVED::Node r;
00148     unsigned num = 0;
00149     while ((r = rm()->lower_bound(Region(addr))))
00150     {
00151         Rm::Region &x = regions.value[num];

```



```

00167         x.start = r->first.start();
00168         x.end   = r->first.end();
00169         x.flags = r->second.flags();
00170
00171         if (++num >= regions.max)
00172             break;
00173
00174         if (x.end >= rm()->max_addr())
00175             break;
00176         addr = x.end + 1;
00177     }
00178     return num;
00179 }
00180
00181 l4_ret_t op_get_areas(L4Re::Rm::Rights, l4_addr_t addr,
00182                     L4::Ipc::Ret_array<L4Re::Rm::Area> areas)
00183 {
00184     typename DERIVED::Node r;
00185     unsigned num = 0;
00186     while ((r = rm()->lower_bound_area(Region(addr))))
00187     {
00188         Rm::Area &x = areas.value[num];
00189         x.start = r->first.start();
00190         x.end   = r->first.end();
00191
00192         if (++num >= areas.max)
00193             break;
00194
00195         if (x.end >= rm()->max_addr())
00196             break;
00197
00198         addr = x.end + 1;
00199     }
00200     return num;
00201 }
00202
00203 private:
00204 static void pager_set_result(L4::Ipc::Opt<L4::Ipc::Snd_fpage> *fp,
00205                             L4::Ipc::Snd_fpage const &f)
00206 { *fp = f; }
00207
00208 static void pager_set_result(L4::Ipc::Opt<L4::Ipc::Snd_fpage> *, ...)
00209 {}
00210
00211 public:
00212 l4_ret_t op_io_page_fault(L4::Io_pager::Rights, l4_fpage_t, l4_umword_t,
00213                          L4::Ipc::Opt<L4::Ipc::Snd_fpage> &)
00214 {
00215     // generate exception
00216     return -L4_ENOMEM;
00217 }
00218
00219 l4_ret_t op_page_fault(L4::Pager::Rights, l4_umword_t addr, l4_umword_t pc,
00220                       L4::Ipc::Opt<L4::Ipc::Snd_fpage> &fp)
00221 {
00222     Dbg(Dbg::Server).printf("page fault: %lx pc=%lx\n", addr, pc);
00223
00224     bool need_w = addr & 2;
00225     bool need_x = addr & 4;
00226
00227     typename DERIVED::Node n = rm()->find(addr);
00228
00229     if (!n || !n->second.memory())
00230     {
00231         Dbg(Dbg::Warn, "rm").printf("unhandled %s page fault at 0x%lx pc=0x%lx\n",
00232                                     need_w ? "write" :
00233                                     need_x ? "instruction" : "read", addr, pc);
00234
00235         // generate exception
00236         return -L4_ENOMEM;
00237     }
00238
00239     if (!(n->second.flags() & L4Re::Rm::F::W) && need_w)
00240     {
00241         Dbg(Dbg::Warn, "rm").printf("write page fault in readonly region at 0x%lx pc=0x%lx\n",
00242                                     addr, pc);
00243
00244         // generate exception
00245         return -L4_EACCESS;
00246     }
00247
00248     if (!(n->second.flags() & L4Re::Rm::F::X) && need_x)
00249     {
00250         Dbg(Dbg::Warn, "rm").printf("instruction page fault in non-exec region at 0x%lx pc=0x%lx\n",
00251                                     addr, pc);
00252
00253         // generate exception
00254         return -L4_EACCESS;
00255     }
00256 }

```

```

00260     }
00261
00262     // This check is optional but avoids doing a map operation that will not
00263     // work. We shall never get here from a page-fault but only from
00264     // artificial page handling.
00265     if (n->second.flags() & (L4Re::Rm::F::Kernel | L4Re::Rm::F::Reserved))
00266     {
00267         Dbg(Dbg::Warn, "rm").printf("page fault handling in kernel-memory provided region or reserved
region at 0x%lx pc=0x%lx\n",
00268                                     addr, pc);
00269         // generate exception
00270         return -L4_ENODEV;
00271     }
00272
00273     typename DERIVED::Region_handler::Ops::Map_result map_res;
00274     if (int err = n->second.map(addr, n->first, need_w, &map_res))
00275     {
00276         Dbg(Dbg::Warn, "rm").printf("mapping for page fault failed with error %d at 0x%lx pc=0x%lx\n",
00277                                     err, addr, pc);
00278         // generate exception
00279         return -L4_ENOMEM;
00280     }
00281
00282     pager_set_result(&fp, map_res);
00283     return L4_EOK;
00284 }
00285
00286 long op_get_info(L4Re::Rm::Rights, l4_addr_t addr,
00287                 L4::Ipc::String<char> &name, L4Re::Rm::Offset &backing_offset)
00288 {
00289 #ifdef CONFIG_L4RE_REGION_INFO
00290     typename DERIVED::Node r = rm()->find(Region(addr));
00291     if (!r)
00292         return -L4_ENOENT;
00293     backing_offset = r->first.backing_offset();
00294     unsigned long i;
00295     char const *src = r->first.name();
00296     unsigned src_len = r->first.name_len();
00297     for (i = 0; i < src_len && i < name.length - 1; ++i)
00298         name.data[i] = src[i];
00299     name.length = i + 1;
00300     name.data[i] = '\0';
00301     return L4_EOK;
00302 #else
00303     (void)addr;
00304     (void)name;
00305     (void)backing_offset;
00306     return -L4_ENOSYS;
00307 #endif
00308 }
00309 };
00310
00311 }}

```

## 16.401 l4/re/shared\_cap File Reference

Shared\_cap / Shared\_del\_cap.

```

#include <l4/re/cap_alloc>
#include <l4/sys/cxx/smart_capability_1x>

```

[illegible]

```
graph BT; A[l4/l4re_vfs/impl/vfs_impl.h] --> B[l4/re/shared_cap]
```

- namespace **L4Re**  
*L4Re C++ Interfaces.*

- `template<typename T>`  
using `L4Re::Shared_cap` = `L4::Detail::Shared_cap_impl<T, L4Re::Smart_count_cap<L4_FP_ALL_SPACES>>`  
*Shared capability that implements automatic free and unmap of the capability selector.*
- `template<typename T>`  
using `L4Re::Shared_del_cap` = `L4::Detail::Shared_cap_impl<T, L4Re::Smart_count_cap<L4_FP_DELETE_OBJ>>`  
*Shared capability that implements automatic free and unmap+delete of the capability selector.*

## Functions

- `template<typename T>`  
`Shared_cap< T > L4Re::make_shared_cap (L4Re::Cap_alloc *ca)`  
*Allocate a capability slot and wrap it in a [Shared\\_cap](#).*
- `template<typename T>`  
`Shared_del_cap< T > L4Re::make_shared_del_cap (L4Re::Cap_alloc *ca)`  
*Allocate a capability slot and wrap it in a [Shared\\_del\\_cap](#).*

### 16.401.1 Detailed Description

`Shared_cap` / `Shared_del_cap`.

Definition in file [shared\\_cap](#).

## 16.402 shared\_cap


[Go to the documentation of this file.](#)

```
00001 // vim:set ft=cpp: -*- Mode: C++ -*-
00006 /*
00007  * (c) 2018 Alexander Warg <alexander.warg@kernkonzept.com>
00008  *
00009  * License: see LICENSE.spdx (in this directory or the directories above)
00010  */
00011
00012 #pragma once
00013
00014 #include <l4/re/cap_alloc>
00015 #include <l4/sys/cxx/smart_capability_1x>
00016
00017 namespace L4Re {
00018
00032 template< typename T >
00033 using Shared_cap
00034     = L4::Detail::Shared_cap_impl<T, L4Re::Smart_count_cap<L4_FP_ALL_SPACES>;
00036 template< typename T >
00037 using shared_cap [[deprecated("Use L4Re::Shared_cap.")]]
00038     = L4::Detail::Shared_cap_impl<T, L4Re::Smart_count_cap<L4_FP_ALL_SPACES>;
00039
00049 template< typename T >
00050 Shared_cap<T>
00051 make_shared_cap(L4Re::Cap_alloc *ca)
00052 { return Shared_cap<T>(ca->alloc<T>(), ca); }
00053
00070 template< typename T >
00071 using Shared_del_cap
00072     = L4::Detail::Shared_cap_impl<T, L4Re::Smart_count_cap<L4_FP_DELETE_OBJ>;
00074 template<typename T>
00075 using shared_del_cap [[deprecated("Use L4Re::Shared_del_cap.")]]
00076     = L4::Detail::Shared_cap_impl<T, L4Re::Smart_count_cap<L4_FP_DELETE_OBJ>;
00077
00087 template< typename T >
00088 Shared_del_cap<T>
00089 make_shared_del_cap(L4Re::Cap_alloc *ca)
00090 { return Shared_del_cap<T>(ca->alloc<T>(), ca); }
00091
00092 } // namespace L4Re
```


### 16.403 l4/re/util/shared\_cap File Reference

`Shared_cap` / `Shared_del_cap`.

```
#include <l4/re/util/cap_alloc>
#include <l4/sys/cxx/smart_capability_1x>
Include dependency graph for shared_cap:
```



This graph shows which files directly or indirectly include this file:



## Namespaces

- namespace [L4Re](#)  
*[L4Re C++ Interfaces](#).*
- namespace [L4Re::Util](#)  
*Documentation of the [L4 Runtime Environment](#) utility functionality in C++.*

## Typedefs

- `template<typename T>`  
`using L4Re::Util::Shared_cap = L4::Detail::Shared_cap_impl<T, L4Re::Util::Smart_count_cap<L4_FP_ALL_SPACES>>`  
*Shared capability that implements automatic free and unmap of the capability selector.*
- `template<typename T>`  
`using L4Re::Util::Shared_del_cap = L4::Detail::Shared_cap_impl<T, L4Re::Util::Smart_count_cap<L4_FP_DELETE_OBJ>>`  
*Shared capability that implements automatic free and unmap+delete of the capability selector.*

## Functions

- `template<typename T>`  
`Shared_cap< T > L4Re::Util::make_shared_cap ()`  
*Allocate a capability slot and wrap it in a [Shared\\_cap](#).*
- `template<typename T>`  
`Shared_del_cap< T > L4Re::Util::make_shared_del_cap ()`  
*Allocate a capability slot and wrap it in a [Shared\\_del\\_cap](#).*

### 16.403.1 Detailed Description

`Shared_cap` / `Shared_del_cap`.

Definition in file [shared\\_cap](#).

## 16.404 shared\_cap


[Go to the documentation of this file.](#)

```
00001 // vim:set ft=cpp: -*- Mode: C++ -*-
00006 /*
00007  * (c) 2017 Alexander Warg <alexander.warg@kernkonzept.com>
00008  *
00009  * License: see LICENSE.spdx (in this directory or the directories above)
00010  */
00011
00012 #pragma once
00013
00014 #include <l4/re/util/cap_alloc>
00015 #include <l4/sys/cxx/smart_capability_1x>
00016
00017 namespace L4Re { namespace Util {
00018
00047 template< typename T >
00048 using Shared_cap
00049     = L4::Detail::Shared_cap_impl<T, L4Re::Util::Smart_count_cap<L4_FP_ALL_SPACES>;
00051 template< typename T >
00052 using shared_cap [[deprecated("Use L4Re::Util::Shared_cap.")]]
00053     = L4::Detail::Shared_cap_impl<T, L4Re::Util::Smart_count_cap<L4_FP_ALL_SPACES>;
00054
00060 template< typename T >
00061 Shared_cap<T>
00062 make_shared_cap()
00063 { return Shared_cap<T>(cap_alloc.alloc<T>()); }
00064
00099 template< typename T >
00100 using Shared_del_cap
00101     = L4::Detail::Shared_cap_impl<T, L4Re::Util::Smart_count_cap<L4_FP_DELETE_OBJ>;
00103 template< typename T >
00104 using shared_del_cap [[deprecated("Use L4Re::Util::Shared_del_cap.")]]
00105     = L4::Detail::Shared_cap_impl<T, L4Re::Util::Smart_count_cap<L4_FP_DELETE_OBJ>;
00106
00112 template< typename T >
00113 Shared_del_cap<T>
00114 make_shared_del_cap()
00115 { return Shared_del_cap<T>(cap_alloc.alloc<T>()); }
00116
00117 }} // namespace L4Re::Util
00118
```


### 16.405 I4/re/unique\_cap File Reference

Unique\_cap / Unique\_del\_cap.

```
#include <l4/re/cap_alloc>
#include <l4/sys/cxx/smart_capability_1x>
Include dependency graph for unique_cap:
```



This graph shows which files directly or indirectly include this file:



## Namespaces

- namespace **L4Re**  
*L4Re C++ Interfaces.*

## Typedefs

- `template<typename T>`  
`using L4Re::Unique_cap = L4::Detail::Unique_cap_impl<T, L4Re::Smart_cap_auto<L4_FP_ALL_SPACES>>`  
*Unique capability that implements automatic free and unmap of the capability selector.*
- `template<typename T>`  
`using L4Re::Unique_del_cap = L4::Detail::Unique_cap_impl<T, L4Re::Smart_cap_auto<L4_FP_DELETE_OBJ>>`  
*Unique capability that implements automatic free and unmap+delete of the capability selector.*

## Functions

- `template<typename T>`  
`Unique_cap< T > L4Re::make_unique_cap (L4Re::Cap_alloc *ca)`  
*Allocate a capability slot and wrap it in an `Unique_cap`.*
- `template<typename T>`  
`Unique_del_cap< T > L4Re::make_unique_del_cap (L4Re::Cap_alloc *ca)`  
*Allocate a capability slot and wrap it in an `Unique_del_cap`.*

## 16.405.1 Detailed Description

`Unique_cap` / `Unique_del_cap`.

Definition in file [unique\\_cap](#).

## 16.406 unique\_cap

[Go to the documentation of this file.](#)

```
00001 // vim:set ft=cpp: -*- Mode: C++ -*-
00006 /*
00007  * (c) 2017 Alexander Warg <alexander.warg@kernkonzept.com>
00008  *
00009  * License: see LICENSE.spdx (in this directory or the directories above)
00010  */
00011
00012 #pragma once
00013
00014 #include <l4/re/cap_alloc>
00015 #include <l4/sys/cxx/smart_capability_lx>
00016
00017 namespace L4Re {
00018
00030 template< typename T >
00031 using Unique_cap
00032     = L4::Detail::Unique_cap_impl<T, L4Re::Smart_cap_auto<L4_FP_ALL_SPACES>;
00034 template< typename T >
00035 using unique_cap [[deprecated("Use L4Re::Unique_cap.")]]
00036     = L4::Detail::Unique_cap_impl<T, L4Re::Smart_cap_auto<L4_FP_ALL_SPACES>;
00037
00047 template< typename T >
00048 Unique_cap<T>
00049 make_unique_cap(L4Re::Cap_alloc *ca)
00050 { return Unique_cap<T>(ca->alloc<T>(), ca); }
00051
00065 template< typename T >
00066 using Unique_del_cap
00067     = L4::Detail::Unique_cap_impl<T, L4Re::Smart_cap_auto<L4_FP_DELETE_OBJ>;
00069 template<typename T>
00070 using unique_del_cap [[deprecated("Use L4Re::Unique_del_cap.")]]
00071     = L4::Detail::Unique_cap_impl<T, L4Re::Smart_cap_auto<L4_FP_DELETE_OBJ>;
00072
00082 template< typename T >
00083 Unique_del_cap<T>
00084 make_unique_del_cap(L4Re::Cap_alloc *ca)
00085 { return Unique_del_cap<T>(ca->alloc<T>(), ca); }
00086
00087 }
```



Unique\_cap / Unique\_del\_cap.

[illegible]

- namespace **L4Re**  
*L4Re C++ Interfaces.*
- namespace **L4Re::Util**

Generated for L4Re by Doxygen

## Typedefs

- `template<typename T>`  
`using L4Re::Util::Unique_cap = L4::Detail::Unique_cap_impl<T, L4Re::Util::Smart_cap_auto<L4_FP_ALL_SPACES>>`  
*Unique capability that implements automatic free and unmap of the capability selector.*
- `template<typename T>`  
`using L4Re::Util::Unique_del_cap = L4::Detail::Unique_cap_impl<T, L4Re::Util::Smart_cap_auto<L4_FP_DELETE_OBJ>>`  
*Unique capability that implements automatic free and unmap+delete of the capability selector.*

## Functions

- `template<typename T>`  
`Unique_cap< T > L4Re::Util::make_unique_cap ()`  
*Allocate a capability slot and wrap it in an `Unique_cap`.*
- `template<typename T>`  
`Unique_del_cap< T > L4Re::Util::make_unique_del_cap ()`  
*Allocate a capability slot and wrap it in an `Unique_del_cap`.*

### 16.407.1 Detailed Description

`Unique_cap` / `Unique_del_cap`.

Definition in file [unique\\_cap](#).

## 16.408 unique\_cap

[Go to the documentation of this file.](#)

```
00001 // vim:set ft=cpp: -*- Mode: C++ -*-
00006 /*
00007  * (c) 2017 Alexander Warg <alexander.warg@kernkonzept.com>
00008  *
00009  * License: see LICENSE.spdx (in this directory or the directories above)
00010  */
00011
00012 #pragma once
00013
00014 #include <l4/re/util/cap_alloc>
00015 #include <l4/sys/cxx/smart_capability_1x>
00016
00017 namespace L4Re { namespace Util {
00018
00042 template< typename T >
00043 using Unique_cap
00044     = L4::Detail::Unique_cap_impl<T, L4Re::Util::Smart_cap_auto<L4_FP_ALL_SPACES>;
00046 template< typename T >
00047 using unique_cap [[deprecated("Use L4Re::Util::Unique_cap.")]]
00048     = L4::Detail::Unique_cap_impl<T, L4Re::Util::Smart_cap_auto<L4_FP_ALL_SPACES>;
00049
00055 template< typename T >
00056 Unique_cap<T>
00057 make_unique_cap()
00058 { return Unique_cap<T>(cap_alloc.alloc<T>()); }
00059
00087 template< typename T >
00088 using Unique_del_cap
00089     = L4::Detail::Unique_cap_impl<T, L4Re::Util::Smart_cap_auto<L4_FP_DELETE_OBJ>;
00091 template< typename T >
00092 using unique_del_cap [[deprecated("Use L4Re::Util::Unique_del_cap.")]]
00093     = L4::Detail::Unique_cap_impl<T, L4Re::Util::Smart_cap_auto<L4_FP_DELETE_OBJ>;
00094
00100 template< typename T >
00101 Unique_del_cap<T>
00102 make_unique_del_cap()
00103 { return Unique_del_cap<T>(cap_alloc.alloc<T>()); }
00104
00105 }}
00106
```

## 16.409 vcon\_svr

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00002 /*
00003  * (c) 2008-2011 Alexander Warg <warg@os.inf.tu-dresden.de>,
00004  *                      Torsten Frenzel <frenzel@os.inf.tu-dresden.de>
00005  *                      Adam Lackorzynski <adam@os.inf.tu-dresden.de>
00006  *                      economic rights: Technische Universität Dresden (Germany)
00007  *
00008  * License: see LICENSE.spdx (in this directory or the directories above)
00009  */
00010 #pragma once
00011
00012 #include <l4/sys/types.h>
00013 #include <l4/sys/vcon>
00014 #include <l4/sys/cxx/ipc_legacy>
00015 #include <l4/cxx/minmax>
00016
00017 namespace L4Re { namespace Util {
00018
00035 template< typename SVR >
00036 class Vcon_svr
00037 {
00038 public:
00039     L4_RPC_LEGACY_DISPATCH(L4::Vcon);
00040
00041     l4_msgtag_t op_dispatch(l4_utcb_t *utcb, l4_msgtag_t tag, L4::Vcon::Rights)
00042     {
00043         l4_msg_regs_t *m = l4_utcb_mr_u(utcb);
00044         L4::Opcode op = m->mr[0] & 0xFFFF;
00045
00046         switch (op)
00047         {
00048             case L4_VCON_WRITE_OP:
00049                 if (tag.words() < 3)
00050                     return l4_msgtag(-L4_ENOREPLY, 0, 0, 0);
00051
00052                 this_vcon()->vcon_write(reinterpret_cast<char const *>(&m->mr[2]),
00053                                         m->mr[1]);
00054                 return l4_msgtag(-L4_ENOREPLY, 0, 0, 0);
00055             case L4_VCON_SET_ATTR_OP:
00056             {
00057                 if (tag.words() < 4)
00058                     return l4_msgtag(-L4_EINVAL, 0, 0, 0);
00059
00060                 auto attr = reinterpret_cast<l4_vcon_attr_t const *>(&m->mr[1]);
00061                 return l4_msgtag(this_vcon()->vcon_set_attr(attr), 0, 0, 0);
00062             }
00063             case L4_VCON_GET_ATTR_OP:
00064             {
00065                 auto attr = reinterpret_cast<l4_vcon_attr_t *>(&m->mr[1]);
00066                 return l4_msgtag(this_vcon()->vcon_get_attr(attr), 4, 0, 0);
00067             }
00068             case L4_VCON_READ_OP:
00069                 break;
00070             default:
00071                 return l4_msgtag(-L4_ENOSYS, 0, 0, 0);
00072         }
00073
00074         unsigned const max_size = L4_VCON_READ_SIZE;
00075         char buf[max_size];
00076
00077         unsigned size = cxx::min<unsigned>(m->mr[0] » 16, max_size);
00078
00079         // Hmm, could we avoid the double copy here?
00080         l4_umword_t v = this_vcon()->vcon_read(buf, size);
00081         unsigned bytes = v & L4_VCON_READ_SIZE_MASK;
00082
00083         if (bytes <= size)
00084             v |= L4_VCON_READ_STAT_DONE;
00085         else
00086             // In case of size == max_size, the returned bytes value is greater than
00087             // the buffer.
00088             bytes = size;
00089
00090         m->mr[0] = v;
00091         __builtin_memcpy(&m->mr[1], buf, bytes);
00092
00093         return l4_msgtag(0, l4_bytes_to_mwords(bytes) + 1, 0, 0);
00094     }
00095
00096     unsigned vcon_read(char *buf, unsigned size) noexcept;
00097     void vcon_write(const char *buf, unsigned size) noexcept;
00098     int vcon_set_attr(l4_vcon_attr_t const *) noexcept

```

```

00101     { return -L4_EOK; }
00102     int vcon_get_attr(l4_vcon_attr_t *attr) noexcept
00103     {
00104         attr->l_flags = attr->o_flags = attr->i_flags = 0;
00105         return -L4_EOK;
00106     }
00107
00108 private:
00109     SVR const *this_vcon() const { return static_cast<SVR const *>(this); }
00110     SVR *this_vcon() { return static_cast<SVR *>(this); }
00111 };
00112
00113 }}

```

## 16.410 goos\_fb

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00002 /*
00003  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00004  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00005  *      economic rights: Technische Universität Dresden (Germany)
00006  *
00007  * License: see LICENSE.spdx (in this directory or the directories above)
00008  */
00009 #pragma once
00010
00011 #include <l4/re/env>
00012 #include <l4/re/namespace>
00013 #include <l4/re/rm>
00014 #include <l4/re/util/cap_alloc>
00015 #include <l4/re/util/env_ns>
00016 #include <l4/re/util/video/goos_fb>
00017 #include <l4/re/video/goos>
00018
00019 namespace L4Re { namespace Util { namespace Video {
00020
00021     class Goos_fb
00022     {
00023     private:
00024         L4::Cap<L4Re::Video::Goos> _goos;
00025         L4Re::Video::View _view;
00026         L4::Cap<L4Re::Dataspace> _buffer;
00027
00028         enum Flags
00029         {
00030             F_dyn_buffer = 0x01,
00031             F_dyn_view   = 0x02,
00032             F_dyn_goos    = 0x04,
00033         };
00034         unsigned _flags;
00035
00036         unsigned _buffer_index;
00037
00038     private:
00039         long init()
00040         {
00041             using namespace L4Re::Video;
00042
00043             Goos::Info gi;
00044             long ret = _goos->info(&gi);
00045             if (ret < 0)
00046                 return ret;
00047
00048             if (gi.has_dynamic_views())
00049             {
00050                 ret = _goos->create_view(&_view);
00051                 if (ret < 0)
00052                     return ret;
00053                 _flags |= F_dyn_view;
00054             }
00055             else // we just assume view 0 to be our's and ignore other possible views
00056                 _view = _goos->view(0);
00057
00058             View::Info vi;
00059             ret = _view.info(&vi);
00060             if (ret < 0)
00061                 return ret;
00062             _buffer = cap_alloc.alloc<L4Re::Dataspace>();
00063             if (!_buffer)
00064                 return -L4_ENOMEM;
00065
00066         }
00067     };

```

```

00068     if (vi.has_static_buffer())
00069     {
00070         ret = _goos->get_static_buffer(vi.buffer_index, _buffer);
00071         if (ret < 0)
00072             return ret;
00073     }
00074     else
00075     {
00076         unsigned long buffer_sz = gi.pixel_info.bytes_per_pixel() * gi.width
00077                                     * gi.height;
00078         ret = _goos->create_buffer(buffer_sz, _buffer);
00079         if (ret < 0)
00080             return ret;
00081
00082         _buffer_index = static_cast<unsigned>(ret);
00083         _flags |= F_dyn_buffer;
00084
00085         // use the allocated buffer, at offset 0
00086         vi.buffer_index = _buffer_index;
00087         vi.buffer_offset = 0;
00088         vi.pixel_info = gi.pixel_info;
00089         vi.bytes_per_line = gi.width * gi.pixel_info.bytes_per_pixel();
00090
00091         // we want a fullscreen view
00092         vi.xpos = 0;
00093         vi.ypos = 0;
00094         vi.width = gi.width;
00095         vi.height = gi.height;
00096
00097         ret = _view.set_info(vi);
00098         if (ret < 0)
00099             return ret;
00100
00101         ret = _view.push_top();
00102         if (ret < 0)
00103             return ret;
00104     }
00105
00106     return 0;
00107 }
00108
00109 Goos_fb(Goos_fb const &);
00110 void operator = (Goos_fb const &);
00111
00112 public:
00113 Goos_fb()
00114 : _goos(L4_INVALID_CAP), _buffer(L4_INVALID_CAP), _flags(0), _buffer_index(0)
00115 {}
00116
00117 long init(L4::Cap<L4Re::Video::Goos> goos)
00118 {
00119     _goos = goos;
00120     return init();
00121 }
00122
00123 long init(char const *name)
00124 {
00125     Env_ns ns;
00126     _goos = ns.query<L4Re::Video::Goos>(name);
00127     if (!_goos)
00128         return _goos.cap();
00129
00130     _flags |= F_dyn_goos;
00131
00132     return init();
00133 }
00134
00135 ~Goos_fb()
00136 {
00137     if (!_goos.is_valid())
00138         return;
00139
00140     if (_flags & F_dyn_view)
00141         _goos->delete_view(_view);
00142
00143     if (_flags & F_dyn_buffer)
00144         _goos->delete_buffer(_buffer_index);
00145
00146     if (_buffer.is_valid())
00147         cap_alloc.free(_buffer);
00148
00149     if (_flags & F_dyn_goos)
00150         cap_alloc.free(_goos);
00151 }
00152
00153 int view_info(L4Re::Video::View::Info *info)
00154 { return _view.info(info); }

```

```

00155
00156 L4Re::Video::View const *view() const { return &_view; }
00157 L4Re::Video::View *view() { return &_view; }
00158
00159 L4::Cap<L4Re::Dataspace> buffer() const { return _buffer; }
00160 void *attach_buffer()
00161 {
00162     void *fb_addr = 0;
00163     if (!_goos)
00164         return nullptr;
00165
00166     long ret = L4Re::Env::env()->rm()
00167         ->attach(&fb_addr, _buffer->size(),
00168             L4Re::Rm::F::Search_addr | L4Re::Rm::F::RW, _buffer,
00169             0, L4_SUPERPAGESHIFT);
00170     if (ret < 0)
00171         return nullptr;
00172
00173     return fb_addr;
00174 }
00175
00176 int refresh(int x, int y, int w, int h)
00177 { return _view.refresh(x, y, w, h); }
00178
00179 L4::Cap<L4Re::Video::Goos> goos() const { return _goos; }
00180 };
00181 }}

```

## 16.411 goos\_svr

```

00001 // vi:set ft=c++: -*- Mode: C++ -*-
00002 /*
00003  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00004  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00005  *      economic rights: Technische Universität Dresden (Germany)
00006  *
00007  * License: see LICENSE.spdx (in this directory or the directories above)
00008  */
00009
00010 #pragma once
00011
00012 #include <l4/re/dataspace>
00013 #include <l4/re/video/goos>
00014 #include <l4/re/video/goos-sys.h>
00015
00016 #include <l4/sys/capability>
00017 #include <l4/sys/cxx/ipc_legacy>
00018
00019 namespace L4Re { namespace Util { namespace Video {
00020
00021     class Goos_svr
00022     {
00023     public:
00024         typedef L4Re::Video::Goos::Rights Rights;
00025     protected:
00026         L4::Cap<L4Re::Dataspace> _fb_ds;
00027         L4Re::Video::Goos::Info _screen_info;
00028         L4Re::Video::View::Info _view_info;
00029     public:
00030         L4_RPC_LEGACY_DISPATCH(L4Re::Video::Goos);
00031         L4::Cap<L4Re::Dataspace> get_fb() const { return _fb_ds; }
00032
00033         L4Re::Video::Goos::Info const *screen_info() const { return &_screen_info; }
00034
00035         L4Re::Video::View::Info const *view_info() const { return &_view_info; }
00036
00037         virtual int refresh(int x, int y, int w, int h)
00038         { (void)x; (void)y; (void)w; (void)h; return -L4_ENOSYS; }
00039
00040         void init_infos()
00041         {
00042             using L4Re::Video::View;
00043
00044             _view_info.flags = View::F_none;
00045
00046             _view_info.view_index = 0;
00047             _view_info.xpos = 0;
00048             _view_info.ypos = 0;
00049             _view_info.width = _screen_info.width;
00050             _view_info.height = _screen_info.height;
00051             _view_info.pixel_info = _screen_info.pixel_info;
00052             _view_info.buffer_index = 0;
00053         }
00054     };
00055 } } }

```

```

00091     }
00092
00096     virtual ~Goos_svr() {}
00097
00098     l4_ret_t op_view_info(Rights, unsigned idx, L4Re::Video::View::Info &info)
00099     {
00100         if (idx != 0)
00101             return -L4_ERANGE;
00102
00103         info = _view_info;
00104         return L4_EOK;
00105     }
00106
00107     l4_ret_t op_info(Rights, L4Re::Video::Goos::Info &info)
00108     {
00109         info = _screen_info;
00110         return L4_EOK;
00111     }
00112
00113     l4_ret_t op_get_static_buffer(Rights, unsigned idx,
00114                                   L4::Ipc::Cap<L4Re::Dataspace> &ds)
00115     {
00116         if (idx != 0)
00117             return -L4_ERANGE;
00118
00119         ds = L4::Ipc::Cap<L4Re::Dataspace>(_fb_ds, L4_CAP_FPAGE_RW);
00120         return L4_EOK;
00121     }
00122
00123     l4_ret_t op_refresh(Rights, int x, int y, int w, int h)
00124     { return refresh(x, y, w, h); }
00125
00126     l4_ret_t op_view_refresh(Rights, unsigned idx, int x, int y, int w, int h)
00127     {
00128         if (idx != 0)
00129             return -L4_ERANGE;
00130
00131         return refresh(x, y, w, h);
00132     }
00133
00134     l4_ret_t op_set_view_info(Rights, unsigned, L4Re::Video::View::Info)
00135     { return -L4_ENOSYS; }
00136
00137     l4_ret_t op_view_stack(Rights, unsigned, unsigned, bool)
00138     { return -L4_ENOSYS; }
00139
00140     l4_ret_t op_delete_view(Rights, unsigned)
00141     { return -L4_ENOSYS; }
00142
00143     l4_ret_t op_create_view(Rights)
00144     { return -L4_ENOSYS; }
00145
00146     l4_ret_t op_create_buffer(Rights, unsigned long,
00147                               L4::Ipc::Cap<L4Re::Dataspace> &)
00148     { return -L4_ENOSYS; }
00149
00150     l4_ret_t op_delete_buffer(Rights, unsigned)
00151     { return -L4_ENOSYS; }
00152 };
00153
00154
00155 }}}

```

## 16.412 colors

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00002 /*
00003  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00004  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00005  *      economic rights: Technische Universität Dresden (Germany)
00006  *
00007  * License: see LICENSE.spdx (in this directory or the directories above)
00008  */
00009
00010 #pragma once
00011
00012 #include <l4/sys/compiler.h>
00013 #include <l4/cxx/minmax>
00014
00015 namespace L4Re { namespace Video {
00016
00021 class L4_EXPORT Color_component
00022 {

```

```

00023 private:
00024     unsigned char _bits;
00025     unsigned char _shift;
00026
00027 public:
00029     Color_component() : _bits(0), _shift(0) {}
00030
00036     Color_component(unsigned char bits, unsigned char shift)
00037     : _bits(bits), _shift(shift) {}
00038
00043     unsigned char size() const { return _bits; }
00044
00049     unsigned char shift() const { return _shift; }
00050
00055     bool operator == (Color_component const &o) const
00056     { return _shift == o._shift && _bits == o._bits; }
00057
00063     int get(unsigned long v) const
00064     {
00065         return ((v > _shift) & ~(~0UL << _bits)) << (16UL - _bits);
00066     }
00067
00073     long unsigned set(int v) const
00074     { return (static_cast<unsigned long>(v) > (16UL - _bits)) << _shift; }
00075
00080     template< typename OUT >
00081     void dump(OUT &s) const
00082     {
00083         s.printf("%d(%d)", static_cast<int>(size()), static_cast<int>(shift()));
00084     }
00085 } __attribute__((packed));
00086
00094 class L4_EXPORT Pixel_info
00095 {
00096 private:
00097     Color_component _r, _g, _b, _a;
00098     unsigned char _bpp;
00099
00100 public:
00105     Color_component const &r() const { return _r; }
00106
00111     Color_component const &g() const { return _g; }
00112
00117     Color_component const &b() const { return _b; }
00118
00123     Color_component const &a() const { return _a; }
00124
00131     Color_component const padding() const
00132     {
00133         unsigned char top_bit = cxx::max<unsigned char>(_r.size() + _r.shift(),
00134                                                         _g.size() + _g.shift());
00135         top_bit = cxx::max<unsigned char>(top_bit, _b.size() + _b.shift());
00136         top_bit = cxx::max<unsigned char>(top_bit, _a.size() + _a.shift());
00137
00138         unsigned char bits = _bpp * 8;
00139
00140         if (top_bit < bits)
00141             return Color_component(bits - top_bit, top_bit);
00142
00143         return Color_component(0, 0);
00144     }
00145
00150     unsigned char bytes_per_pixel() const { return _bpp; }
00151
00156     unsigned char bits_per_pixel() const
00157     { return _r.size() + _g.size() + _b.size() + _a.size(); }
00158
00163     bool has_alpha() const { return _a.size() > 0; }
00164
00169     void r(Color_component const &c) { _r = c; }
00170
00175     void g(Color_component const &c) { _g = c; }
00176
00181     void b(Color_component const &c) { _b = c; }
00182
00187     void a(Color_component const &c) { _a = c; }
00188
00193     void bytes_per_pixel(unsigned char bpp) { _bpp = bpp; }
00194
00198     Pixel_info() : _bpp(0) {};
00199
00212     Pixel_info(unsigned char bpp, char r, char rs, char g, char gs,
00213                char b, char bs, char a = 0, char as = 0)
00214     : _r(r, rs), _g(g, gs), _b(b, bs), _a(a, as), _bpp(bpp)
00215     {}
00216
00223     template<typename VBI>

```



```

00224     explicit Pixel_info(VBI const *vbi)
00225     : _r(vbi->red_mask_size, vbi->red_field_position),
00226       _g(vbi->green_mask_size, vbi->green_field_position),
00227       _b(vbi->blue_mask_size, vbi->blue_field_position),
00228       _bpp((vbi->bits_per_pixel + 7) / 8)
00229     {}
00230
00236     bool operator == (Pixel_info const &o) const
00237     {
00238         return _r == o._r && _g == o._g && _b == o._b && _a == o._a && _bpp == o._bpp;
00239     }
00240
00245     template< typename OUT >
00246     void dump(OUT &s) const
00247     {
00248         s.printf("RGBA(%d):%d(%d):%d(%d):%d(%d)",
00249                 static_cast<int>(bytes_per_pixel()),
00250                 static_cast<int>(r().size()), static_cast<int>(r().shift()),
00251                 static_cast<int>(g().size()), static_cast<int>(g().shift()),
00252                 static_cast<int>(b().size()), static_cast<int>(b().shift()),
00253                 static_cast<int>(a().size()), static_cast<int>(a().shift()));
00254     }
00255 };
00256
00257
00258 }}
00259
00260

```

## 16.413 goos

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00002 /*
00003  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00004  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00005  *      economic rights: Technische Universität Dresden (Germany)
00006  *
00007  * License: see LICENSE.spdx (in this directory or the directories above)
00008  */
00009 #pragma once
00010
00011 #include <l4/sys/capability>
00012 #include <l4/re/dataspace>
00013 #include <l4/re/video/colors>
00014 #include <l4/sys/cxx/ipc_iface>
00015
00016 namespace L4Re { namespace Video {
00017
00026     class L4_EXPORT Goos;
00027
00039     class L4_EXPORT View
00040     {
00041     private:
00042         friend class Goos;
00043
00044         L4::Cap<Goos> _goos;
00045         unsigned _view_idx;
00046
00047         View(l4_cap_idx_t goos, unsigned idx)
00048         : _goos(goos), _view_idx(_goos.is_valid() ? idx : ~0U) {}
00049
00050         unsigned view_index() const noexcept
00051         { return _goos.is_valid() ? _view_idx : ~0U; }
00052
00053     public:
00054         View() : _goos(L4::Cap<Goos>::Invalid), _view_idx(~0U) {}
00055
00059         enum Flags
00060         {
00061             F_none                = 0x00,
00062             F_set_buffer           = 0x01,
00063             F_set_buffer_offset    = 0x02,
00064             F_set_bytes_per_line   = 0x04,
00065             F_set_pixel            = 0x08,
00066             F_set_position         = 0x10,
00067             F_dyn_allocated        = 0x20,
00068             F_set_background       = 0x40,
00069             F_set_flags            = 0x80,
00070
00072             F_fully_dynamic        = F_set_buffer | F_set_buffer_offset | F_set_bytes_per_line
00073                                   | F_set_pixel | F_set_position | F_dyn_allocated,
00074         };
00075

```

```

00082 enum V_flags
00083 {
00084     F_above          = 0x1000,
00085     F_flags_mask     = 0xff000,
00086 };
00087
00091 struct Info
00092 {
00093     unsigned flags          = 0;
00094     unsigned view_index     = 0;
00095
00096     unsigned long xpos      = 0;
00097     unsigned long ypos      = 0;
00098     unsigned long width     = 0;
00099     unsigned long height    = 0;
00100     unsigned long buffer_offset = 0;
00101     unsigned long bytes_per_line = 0;
00102     Pixel_info pixel_info;
00103     unsigned buffer_index   = 0;
00104
00106     bool has_static_buffer() const { return !(flags & F_set_buffer); }
00108     bool has_static_buffer_offset() const { return !(flags & F_set_buffer_offset); }
00109
00111     bool has_set_buffer() const { return flags & F_set_buffer; }
00113     bool has_set_buffer_offset() const { return flags & F_set_buffer_offset; }
00115     bool has_set_bytes_per_line() const { return flags & F_set_bytes_per_line; }
00117     bool has_set_pixel() const { return flags & F_set_pixel; }
00119     bool has_set_position() const { return flags & F_set_position; }
00120
00122     template< typename OUT >
00123     void dump(OUT &s) const
00124     {
00125         s.printf("View::Info:\n"
00126             "  flags: %x\n"
00127             "  size: %ldx%ld\n"
00128             "  pos: %ldx%ld\n"
00129             "  bytes_per_line: %ld\n"
00130             "  buffer_offset: %lx\n"
00131             "  ",
00132             flags, width, height, xpos, ypos,
00133             bytes_per_line, buffer_offset);
00134         pixel_info.dump(s);
00135         s.printf("\n");
00136     }
00137 };
00138
00146 int info(Info *info) const noexcept;
00147
00158 int set_info(Info const &info) const noexcept;
00159
00171 int set_viewport(int scr_x, int scr_y, int w, int h, unsigned long buf_offset) const noexcept;
00172
00182 int stack(View const &pivot, bool behind = true) const noexcept;
00183
00185 int push_top() const noexcept
00186 { return stack(View(), true); }
00187
00189 int push_bottom() const noexcept
00190 { return stack(View(), false); }
00191
00202 int refresh(int x, int y, int w, int h) const noexcept;
00203
00205 bool valid() const { return _goos.is_valid(); }
00206 };
00207
00208
00223 class L4_EXPORT Goos :
00224     public L4::Kobject_t<Goos, L4::Kobject, L4RE_PROTO_GOOS>
00225 {
00226 public:
00228     enum Flags
00229     {
00230         F_auto_refresh    = 0x01,
00231         F_pointer         = 0x02,
00232         F_dynamic_views   = 0x04,
00233         F_dynamic_buffers = 0x08,
00234     };
00235
00237     struct Info
00238     {
00239         unsigned long width;
00240         unsigned long height;
00241         unsigned flags;
00242         unsigned num_static_views;
00243         unsigned num_static_buffers;
00244         Pixel_info pixel_info;
00245     };

```

```

00248     bool auto_refresh() const { return flags & F_auto_refresh; }
00250     bool has_pointer() const { return flags & F_pointer; }
00252     bool has_dynamic_views() const { return flags & F_dynamic_views; }
00254     bool has_dynamic_buffers() const { return flags & F_dynamic_buffers; }
00255
00256     Info()
00257     : width(0), height(0), flags(0), num_static_views(0),
00258       num_static_buffers(0) {}
00259 };
00260
00268     L4_INLINE_RPC(l4_ret_t, info, (Info *info));
00269
00278     L4_RPC(l4_ret_t, get_static_buffer, (unsigned idx,
00279                                         L4::Ipc::Out<L4::Cap<L4Re::Dataspace> > rbuf));
00280
00289     L4_RPC(l4_ret_t, create_buffer, (unsigned long size,
00290                                     L4::Ipc::Out<L4::Cap<L4Re::Dataspace> > rbuf));
00291
00299     L4_INLINE_RPC(l4_ret_t, delete_buffer, (unsigned idx));
00300
00301     // Use a wrapper for this RPC as we encapsulate the View
00302     L4_INLINE_RPC_NF(l4_ret_t, create_view, ());
00303
00312     l4_ret_t create_view(View *view, l4_utcb_t *utcb = l4_utcb()) const noexcept
00313     {
00314         l4_ret_t r = create_view_t::call(c(), utcb);
00315         if (r < 0)
00316             return r;
00317         *view = View(cap(), r);
00318         return r;
00319     }
00320
00321     // Use a wrapper as Views are encapsulated
00322     L4_INLINE_RPC_NF(l4_ret_t, delete_view, (unsigned index));
00323
00332     l4_ret_t delete_view(View const &v, l4_utcb_t *utcb = l4_utcb()) const noexcept
00333     {
00334         return delete_view_t::call(c(), v._view_idx, utcb);
00335     }
00336
00342     View view(unsigned index) const noexcept;
00343
00347     L4_INLINE_RPC(l4_ret_t, refresh, (int x, int y, int w, int h));
00348
00349     // those are used by the View
00350     L4_INLINE_RPC(l4_ret_t, view_info, (unsigned index, View::Info *info));
00351     L4_INLINE_RPC(l4_ret_t, set_view_info, (unsigned index, View::Info const &info));
00352     L4_INLINE_RPC(l4_ret_t, view_stack, (unsigned index, unsigned pivot, bool behind));
00353     L4_INLINE_RPC(l4_ret_t, view_refresh, (unsigned index, int x, int y, int w, int h));
00354
00355     typedef L4::Typeid::Rpcs<
00356         info_t, get_static_buffer_t, create_buffer_t, create_view_t, delete_buffer_t,
00357         delete_view_t, view_info_t, set_view_info_t, view_stack_t, view_refresh_t,
00358         refresh_t
00359     > Rpcs;
00360 };
00361
00362 inline View
00363 Goos::view(unsigned index) const noexcept
00364 { return View(cap(), index); }
00365
00366 inline int
00367 View::info(Info *info) const noexcept
00368 { return _goos->view_info(_view_idx, info); }
00369
00370 inline int
00371 View::set_info(Info const &info) const noexcept
00372 { return _goos->set_view_info(_view_idx, info); }
00373
00374 inline int
00375 View::stack(View const &pivot, bool behind) const noexcept
00376 { return _goos->view_stack(_view_idx, pivot._view_idx, behind); }
00377
00378 inline int
00379 View::refresh(int x, int y, int w, int h) const noexcept
00380 { return _goos->view_refresh(_view_idx, x, y, w, h); }
00381
00382 inline int
00383 View::set_viewport(int scr_x, int scr_y, int w, int h,
00384                   unsigned long buf_offset) const noexcept
00385 {
00386     Info i;
00387     i.flags = F_set_buffer_offset | F_set_position;
00388     i.buffer_offset = buf_offset;
00389     i.buffer_index = 0;
00390     i.view_index = 0;
00391     i.bytes_per_line = 0;


```

```
00392     i.pixel_info = Pixel_info();
00393     i.xpos = scr_x;
00394     i.ypos = scr_y;
00395     i.width = w;
00396     i.height = h;
00397     return set_info(i);
00398 }
00399
00400 }
```

## 16.414 I4/re/video/goos-sys.h File Reference

Goos protocol definition.

This graph shows which files directly or indirectly include this file:



### Namespaces

- namespace [L4Re](#)  
*L4Re C++ Interfaces.*

### Enumerations

- enum [L4Re::Video::Goos\\_::Opcodes](#)  
*Frame buffer communication-protocol opcodes.*

### 16.414.1 Detailed Description

Goos protocol definition.

Definition in file [goos-sys.h](#).

## 16.415 goos-sys.h

[Go to the documentation of this file.](#)

```

00001 #pragma once
00002 /*
00003  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00004  * Alexander Warg <warg@os.inf.tu-dresden.de>,
00005  * Björn Döbel <doebel@os.inf.tu-dresden.de>
00006  *
00007  * economic rights: Technische Universität Dresden (Germany)
00008  *
00009  * License: see LICENSE.spdx (in this directory or the directories above)
00010  */
00011
00012 namespace L4Re { namespace Video {
00013     namespace Goos_
00014     {
00015         enum Opcodes
00016         {
00017             Info, Get_buffer, Create_buffer, Create_view,
00018             Delete_buffer, Delete_view,
00019             View_info, View_set_info, View_stack, View_refresh,
00020             Screen_refresh
00021         };
00022     };
00023 } }


```

**16.416** **view**

```
00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00002 /*
00003  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00004  * Alexander Warg <warg@os.inf.tu-dresden.de>
00005  * economic rights: Technische Universität Dresden (Germany)
00006  *
00007  * License: see LICENSE.spdx (in this directory or the directories above)
00008  */
00009 #pragma once
00010
00011 #include <l4/re/video/goos>
00012
```

## 16.417 14/shmc/ringbuf.h File Reference

```
#include <l4/shmc/shmc.h>
#include <l4/util/assert.h>
#include <l4/sys/compiler.h>
#include <l4/sys/thread.h>
Include dependency graph for ringbuf.h:
```



## Data Structures

- struct [l4shmc\\_ringbuf\\_head\\_t](#)  
*Head field of a ring buffer.*
- struct [l4shmc\\_ringbuf\\_t](#)  
*Ring buffer.*

## Macros

- #define [L4SHMC\\_RINGBUF\\_HEAD](#)(ringbuf)  
*Get ring buffer head pointer.*
- #define [L4SHMC\\_RINGBUF\\_DATA](#)(ringbuf)  
*Get ring buffer data pointer.*
- #define [L4SHMC\\_RINGBUF\\_DATA\\_SIZE](#)(ringbuf)  
*Get size of data area.*

## Functions

- int [l4shmc\\_rb\\_init\\_buffer](#) ([l4shmc\\_ringbuf\\_t](#) \*buf, [l4shmc\\_area\\_t](#) \*area, char const \*chunk\_name, char const \*signal\_name, unsigned size)  
*Initialize a ring buffer by creating an SHMC chunk and the corresponding signals.*
- void [l4shmc\\_rb\\_deinit\\_buffer](#) ([l4shmc\\_ringbuf\\_t](#) \*buf)  
*De-init a ring buffer.*
- int [l4shmc\\_rb\\_attach\\_sender](#) ([l4shmc\\_ringbuf\\_t](#) \*buf, char const \*signal\_name, [l4\\_cap\\_idx\\_t](#) owner)  
*Attach to sender signal of a ring buffer.*
- char \* [l4shmc\\_rb\\_sender\\_alloc\\_packet](#) ([l4shmc\\_ringbuf\\_head\\_t](#) \*head, unsigned psize)  
*Allocate a packet of a given size within the ring buffer.*
- void [l4shmc\\_rb\\_sender\\_put\\_data](#) ([l4shmc\\_ringbuf\\_t](#) \*buf, char \*addr, char \*data, unsigned dsize)  
*Copy data into a previously allocated packet.*
- int [l4shmc\\_rb\\_sender\\_next\\_copy\\_in](#) ([l4shmc\\_ringbuf\\_t](#) \*buf, char \*data, unsigned size, int block\_if\_necessary)  
*Copy in packet from an external data source.*
- void [l4shmc\\_rb\\_sender\\_commit\\_packet](#) ([l4shmc\\_ringbuf\\_t](#) \*buf)  
*Tell the consumer that new data is available.*
- int [l4shmc\\_rb\\_init\\_receiver](#) ([l4shmc\\_ringbuf\\_t](#) \*buf, [l4shmc\\_area\\_t](#) \*area, char const \*chunk\_name, char const \*signal\_name)  
*Initialize receive buffer.*
- void [l4shmc\\_rb\\_attach\\_receiver](#) ([l4shmc\\_ringbuf\\_t](#) \*buf, [l4\\_cap\\_idx\\_t](#) owner)  
*Attach to receiver signal of a ring buffer.*
- int [l4shmc\\_rb\\_receiver\\_wait\\_for\\_data](#) ([l4shmc\\_ringbuf\\_t](#) \*buf, int blocking)  
*Check if (and optionally block until) new data is ready.*
- int [l4shmc\\_rb\\_receiver\\_copy\\_out](#) ([l4shmc\\_ringbuf\\_head\\_t](#) \*head, char \*target, unsigned \*tsize)  
*Copy data out of the buffer.*
- void [l4shmc\\_rb\\_receiver\\_notify\\_done](#) ([l4shmc\\_ringbuf\\_t](#) \*buf)  
*Notify producer that space is available.*
- int [l4shmc\\_rb\\_receiver\\_read\\_next\\_size](#) ([l4shmc\\_ringbuf\\_head\\_t](#) \*head)  
*Have a look at the ring buffer and see which size the next packet to be read has.*

## 16.417.1 Function Documentation

### 16.417.1.1 l4shmc\_rb\_attach\_receiver()

```
void l4shmc_rb_attach_receiver (  
    l4shmc_ringbuf_t * buf,  
    l4_cap_idx_t owner)
```

Attach to receiver signal of a ring buffer.

Attach owner to the receiver-side signal of a ring buffer, which is triggered whenever new data has been produced.

This is split from initialization, because you may not know the owner cap when initializing the buffer.

#### Parameters

<i>buf</i>	pointer to ring buffer struct
<i>owner</i>	owner thread

References [L4\\_CV](#).

### 16.417.1.2 l4shmc\_rb\_attach\_sender()

```
int l4shmc_rb_attach_sender (  
    l4shmc_ringbuf_t * buf,  
    char const * signal_name,  
    l4_cap_idx_t owner)
```

Attach to sender signal of a ring buffer.

Attach owner to the sender-side signal of a ring buffer, which is triggered whenever new space has been freed in the buffer for the sender to write to.

This is split from initialization, because you may not know the owner cap when initializing the buffer.

#### Parameters

<i>buf</i>	pointer to ring buffer struct
<i>signal_name</i>	signal base name
<i>owner</i>	owner thread

#### Returns

0 on success, error otherwise

References [L4\\_CV](#).

### 16.417.1.3 l4shmc\_rb\_deinit\_buffer()

```
void l4shmc_rb_deinit_buffer (
    l4shmc_ringbuf_t * buf)
```

De-init a ring buffer.

#### Parameters

<i>buf</i>	pointer to ring buffer struct
------------	-------------------------------

References [L4\\_CV](#).

### 16.417.1.4 l4shmc\_rb\_init\_buffer()

```
int l4shmc_rb_init_buffer (
    l4shmc_ringbuf_t * buf,
    l4shmc_area_t * area,
    char const * chunk_name,
    char const * signal_name,
    unsigned size)
```

Initialize a ring buffer by creating an SHMC chunk and the corresponding signals.

This needs to be done by one of the participating parties when setting up communication channel.

#### Precondition

area has been attached using [l4shmc\\_attach\(\)](#).

#### Parameters

<i>buf</i>	pointer to ring buffer struct
<i>area</i>	pointer to SHMC area
<i>chunk_name</i>	name of SHMC chunk to create in area
<i>signal_name</i>	base name for SHMC signals to create
<i>size</i>	chunk size

#### Returns

0 on success, error otherwise

References [L4\\_CV](#).



### 16.417.1.5 l4shmc\_rb\_init\_receiver()

```
int l4shmc_rb_init_receiver (
    l4shmc_ringbuf_t * buf,
    l4shmc_area_t * area,
    char const * chunk_name,
    char const * signal_name)
```

Initialize receive buffer.

Initialize the receiver-side of a ring buffer. This requires the underlying SHMC chunk and the corresponding signals to be valid already (read: to be initialized by the sender).

#### Precondition

chunk & signals have been created and initialized by the sender side

#### Parameters

<i>buf</i>	pointer to ring buffer struct
<i>area</i>	pointer to SHMC area
<i>chunk_name</i>	name of SHMC chunk to create in area
<i>signal_name</i>	base name for SHMC signals to create

#### Returns

0 on success, error otherwise

References [L4\\_CV](#).

### 16.417.1.6 l4shmc\_rb\_receiver\_copy\_out()

```
int l4shmc_rb_receiver_copy_out (
    l4shmc_ringbuf_head_t * head,
    char * target,
    unsigned * tsize)
```

Copy data out of the buffer.

#### Parameters

	<i>head</i>	ring buffer head pointer
	<i>target</i>	valid target buffer
<i>in, out</i>	<i>tsize</i>	size of target buffer (must be $\geq$ packet size!); contains the real data size

#### Returns

0 on success, negative error otherwise

References [L4\\_CV](#).

#### 16.417.1.7 l4shmc\_rb\_receiver\_notify\_done()

```
void l4shmc_rb_receiver_notify_done (  
    l4shmc_ringbuf_t * buf)
```

Notify producer that space is available.

##### Parameters

<i>buf</i>	pointer to ring buffer struct
------------	-------------------------------

References [L4\\_CV](#).

#### 16.417.1.8 l4shmc\_rb\_receiver\_read\_next\_size()

```
int l4shmc_rb_receiver_read_next_size (  
    l4shmc_ringbuf_head_t * head)
```

Have a look at the ring buffer and see which size the next packet to be read has.

Does not modify anything.

##### Returns

size of next buffer or -1 if no data available

References [L4\\_CV](#), and [L4\\_END\\_DECLS](#).

#### 16.417.1.9 l4shmc\_rb\_receiver\_wait\_for\_data()

```
int l4shmc_rb_receiver_wait_for_data (  
    l4shmc_ringbuf_t * buf,  
    int blocking)
```

Check if (and optionally block until) new data is ready.

##### Parameters

<i>buf</i>	pointer to ring buffer struct
<i>blocking</i>	block if data is not available immediately

Returns immediately, if data is available.

##### Returns

0 success, data available, != 0 otherwise

References [L4\\_CV](#).

#### 16.417.1.10 l4shmc\_rb\_sender\_alloc\_packet()

```
char * l4shmc_rb_sender_alloc_packet (
    l4shmc_ringbuf_head_t * head,
    unsigned psize)
```

Allocate a packet of a given size within the ring buffer.

This packet may wrap around at the end of the buffer. Users need to be aware of that.

##### Parameters

<i>head</i>	ring buffer head pointer
<i>psize</i>	packet size

##### Returns

valid address on success

##### Return values

<i>NULL</i>	if not enough space available
-------------	-------------------------------

References [L4\\_CV](#).

#### 16.417.1.11 l4shmc\_rb\_sender\_commit\_packet()

```
void l4shmc_rb_sender_commit_packet (
    l4shmc_ringbuf_t * buf)
```

Tell the consumer that new data is available.

##### Parameters

<i>buf</i>	pointer to ring buffer struct
------------	-------------------------------

References [L4\\_CV](#).

#### 16.417.1.12 l4shmc\_rb\_sender\_next\_copy\_in()

```
int l4shmc_rb_sender_next_copy_in (
    l4shmc_ringbuf_t * buf,
    char * data,
    unsigned size,
    int block_if_necessary)
```

Copy in packet from an external data source.

This is the function you'll want to use. Just pass it a buffer pointer and let the lib do the work.

**Parameters**

<i>buf</i>	pointer to ring buffer struct
<i>data</i>	valid buffer
<i>size</i>	data size
<i>block_if_necessary</i>	bool: block if buffer currently full

**Return values**

0	on success
-L4_ENOMEM	if block == false and no space available

References [L4\\_CV](#).

**16.417.1.13 l4shmc\_rb\_sender\_put\_data()**

```
void l4shmc_rb_sender_put_data (
    l4shmc_ringbuf_t * buf,
    char * addr,
    char * data,
    unsigned dsize)
```

Copy data into a previously allocated packet.

This function is wrap-around aware.

**Parameters**

<i>buf</i>	pointer to ring buffer struct
<i>addr</i>	valid destination (allocate with <code>alloc_packet()</code> )
<i>data</i>	data source
<i>dsize</i>	data size

References [L4\\_CV](#).

**16.418 ringbuf.h**

[Go to the documentation of this file.](#)

```
00001 /*
00002  * (c) 2010 Björn Döbel <doebel@os.inf.tu-dresden.de>
00003  *     economic rights: Technische Universität Dresden (Germany)
00004  * This file is part of TUD:OS and distributed under the terms of the
00005  * GNU Lesser General Public License 2.1.
00006  * Please see the COPYING-LGPL-2.1 file for details.
00007 */
00008
00012 #pragma once
00013
00014 #include <l4/shmc/shmc.h>
00015 #include <l4/util/assert.h>
```

```

00016 #include <l4/sys/compiler.h>
00017 #include <l4/sys/thread.h>
00018
00019 L4_BEGIN_DECLS
00020
00035
00046
00047 /*
00048  * Turn on ringbuf poisoning. This will add magic values to the ringbuf
00049  * header as well as each packet header and check that these values are
00050  * valid all the time.
00051  */
00052 #define L4SHMC_RINGBUF_POISONING 1
00053
00059 typedef struct
00060 {
00061     volatile l4_uint32_t lock;
00062     unsigned data_size;
00063     #if L4SHMC_RINGBUF_POISONING
00064         char magic1;
00065     #endif
00066     unsigned next_read;
00067     unsigned next_write;
00068     #if L4SHMC_RINGBUF_POISONING
00069         char magic2;
00070     #endif
00071     unsigned bytes_filled;
00072     unsigned sender_waits;
00073     #if L4SHMC_RINGBUF_POISONING
00074         char magic3;
00075     #endif
00076     char data[];
00077 } l4shmc_ringbuf_head_t;
00078
00079
00085 typedef struct
00086 {
00087     l4shmc_area_t *_area;
00088     l4_cap_idx_t _owner;
00089     l4shmc_chunk_t _chunk;
00090     unsigned _size;
00091     char *_chunkname;
00092     char *_signame;
00093     l4shmc_ringbuf_head_t *_addr;
00094     l4shmc_signal_t _signal_full;
00095     l4shmc_signal_t _signal_empty;
00096 } l4shmc_ringbuf_t;
00097
00098
00105 #define L4SHMC_RINGBUF_HEAD(ringbuf) ((l4shmc_ringbuf_head_t*) ((ringbuf)->_addr))
00106
00107
00114 #define L4SHMC_RINGBUF_DATA(ringbuf) (L4SHMC_RINGBUF_HEAD(ringbuf)->data)
00115
00116
00123 #define L4SHMC_RINGBUF_DATA_SIZE(ringbuf) ((ringbuf)->_size - sizeof(l4shmc_ringbuf_head_t))
00124
00125 enum lock_content
00126 {
00127     lock_cont_min = 4,
00128     locked = 5,
00129     unlocked = 6,
00130     lock_cont_max = 7,
00131 };
00132
00133 static L4_CV inline void l4shmc_rb_lock(l4shmc_ringbuf_head_t *head)
00134 {
00135     ASSERT_NOT_NULL(head);
00136     ASSERT_ASSERT(head->lock > lock_cont_min);
00137     ASSERT_ASSERT(head->lock < lock_cont_max);
00138
00139     while (!l4util_cmpxchg32(&head->lock, unlocked, locked))
00140         l4_thread_yield();
00141 }
00142
00143
00144 static L4_CV inline void l4shmc_rb_unlock(l4shmc_ringbuf_head_t *head)
00145 {
00146     ASSERT_NOT_NULL(head);
00147     ASSERT_ASSERT(head->lock > lock_cont_min);
00148     ASSERT_ASSERT(head->lock < lock_cont_max);
00149
00150     head->lock = unlocked;
00151 }
00152
00153 /*****
00154  * Initialization *

```

```

00155  *****/
00156
00173 L4_CV int  l4shmc_rb_init_buffer(l4shmc_ringbuf_t *buf, l4shmc_area_t *area,
00174                                     char const *chunk_name,
00175                                     char const *signal_name, unsigned size);
00176
00182 L4_CV void l4shmc_rb_deinit_buffer(l4shmc_ringbuf_t *buf);
00183
00184
00185
00186 /*****
00187  *    RINGBUF SENDER    *
00188  *****/
00189
00206 L4_CV int l4shmc_rb_attach_sender(l4shmc_ringbuf_t *buf, char const *signal_name,
00207                                     l4_cap_idx_t owner);
00208
00209
00222 L4_CV char *l4shmc_rb_sender_alloc_packet(l4shmc_ringbuf_head_t *head,
00223                                             unsigned psize);
00224
00225
00236 L4_CV void l4shmc_rb_sender_put_data(l4shmc_ringbuf_t *buf, char *addr,
00237                                       char *data, unsigned dsize);
00238
00239
00254 L4_CV int  l4shmc_rb_sender_next_copy_in(l4shmc_ringbuf_t *buf, char *data,
00255                                             unsigned size, int block_if_necessary);
00256
00257
00263 L4_CV void l4shmc_rb_sender_commit_packet(l4shmc_ringbuf_t *buf);
00264
00265
00266 /*****
00267  *    RINGBUF RECEIVER    *
00268  *****/
00269
00286 L4_CV int  l4shmc_rb_init_receiver(l4shmc_ringbuf_t *buf, l4shmc_area_t *area,
00287                                       char const *chunk_name,
00288                                       char const *signal_name);
00289
00290
00303 L4_CV void l4shmc_rb_attach_receiver(l4shmc_ringbuf_t *buf, l4_cap_idx_t owner);
00304
00305
00316 L4_CV int l4shmc_rb_receiver_wait_for_data(l4shmc_ringbuf_t *buf, int blocking);
00317
00318
00328 L4_CV int  l4shmc_rb_receiver_copy_out(l4shmc_ringbuf_head_t *head, char *target,
00329                                           unsigned *tsize);
00330
00331
00337 L4_CV void l4shmc_rb_receiver_notify_done(l4shmc_ringbuf_t *buf);
00338
00339
00346 L4_CV int l4shmc_rb_receiver_read_next_size(l4shmc_ringbuf_head_t *head);
00347
00348 L4_END_DECLS

```

## 16.419 l4/shmc/shmc.h File Reference


Shared memory library header file.

```


#include <l4/sys/compiler.h>
#include <l4/sys/linkage.h>
#include <l4/sys/types.h>
#include <l4/sys/err.h>
#include <l4/shmc/types.h>
#include <l4/shmc/internal.h>

```

Include dependency graph for shmc.h:



This graph shows which files directly or indirectly include this file:



## Functions

- [L4\\_BEGIN\\_DECLS](#) long [l4shmc\\_create](#) (char const \*shmc\_name)  
*Create a shared memory area.*
- long [l4shmc\\_attach](#) (char const \*shmc\_name, l4shmc\_area\_t \*shmarea)  
*Attach to a shared memory area.*
- long [l4shmc\\_get\\_client\\_nr](#) (l4shmc\_area\_t const \*shmarea)  
*Determine the client number of the shared memory region.*
- long [l4shmc\\_mark\\_client\\_initialized](#) (l4shmc\_area\_t \*shmarea)  
*Mark this shared memory client as 'initialized'.*
- long [l4shmc\\_get\\_initialized\\_clients](#) (l4shmc\_area\_t \*shmarea, [l4\\_umword\\_t](#) \*bitmask)  
*Fetch the `_clients_init_done` bitmask of the shared memory area.*
- long [l4shmc\\_add\\_chunk](#) (l4shmc\_area\_t \*shmarea, char const \*chunk\_name, [l4\\_umword\\_t](#) chunk\_capacity, l4shmc\_chunk\_t \*chunk)  
*Add a chunk in the shared memory area.*

- long [l4shmc\\_add\\_signal](#) (l4shmc\_area\_t \*shmarea, char const \*signal\_name, l4shmc\_signal\_t \*signal)  
*Add a signal for the shared memory area.*
- long [l4shmc\\_trigger](#) (l4shmc\_signal\_t \*signal)  
*Trigger a signal.*
- long [l4shmc\\_chunk\\_try\\_to\\_take](#) (l4shmc\_chunk\_t \*chunk)  
*Try to mark chunk busy.*
- long [l4shmc\\_chunk\\_try\\_to\\_take\\_for\\_writing](#) (l4shmc\_chunk\_t \*chunk)  
*Try to mark chunk busy writing.*
- long [l4shmc\\_chunk\\_try\\_to\\_take\\_for\\_overwriting](#) (l4shmc\_chunk\_t \*chunk)  
*Try to mark the chunk busy writing after it was ready for reading.*
- long [l4shmc\\_chunk\\_try\\_to\\_take\\_for\\_reading](#) (l4shmc\_chunk\_t \*chunk)  
*Try to mark chunk busy reading.*
- long [l4shmc\\_chunk\\_ready](#) (l4shmc\_chunk\_t \*chunk, [l4\\_umword\\_t](#) size)  
*Mark chunk as filled (ready).*
- long [l4shmc\\_chunk\\_ready\\_sig](#) (l4shmc\_chunk\_t \*chunk, [l4\\_umword\\_t](#) size)  
*Mark chunk as filled (ready) and signal consumer.*
- long [l4shmc\\_get\\_chunk](#) (l4shmc\_area\_t \*shmarea, char const \*chunk\_name, l4shmc\_chunk\_t \*chunk)  
*Get chunk out of shared memory area.*
- long [l4shmc\\_get\\_chunk\\_to](#) (l4shmc\_area\_t \*shmarea, char const \*chunk\_name, [l4\\_umword\\_t](#) timeout\_ms, l4shmc\_chunk\_t \*chunk)  
*Get chunk out of shared memory area, with timeout.*
- long [l4shmc\\_iterate\\_chunk](#) (l4shmc\_area\_t const \*shmarea, char const \*\*chunk\_name, long offs)  
*Iterate over names of all existing chunks.*
- long [l4shmc\\_attach\\_signal](#) (l4shmc\_area\_t \*shmarea, char const \*signal\_name, [l4\\_cap\\_idx\\_t](#) thread, l4shmc\_signal\_t \*signal)  
*Attach to signal.*
- long [l4shmc\\_get\\_signal](#) (l4shmc\_area\_t \*shmarea, char const \*signal\_name, l4shmc\_signal\_t \*signal)  
*Get signal object from the shared memory area.*
- long [l4shmc\\_enable\\_signal](#) (l4shmc\_signal\_t \*signal)  
*Enable a signal.*
- long [l4shmc\\_enable\\_chunk](#) (l4shmc\_chunk\_t \*chunk)  
*Enable a signal connected with a chunk.*
- long [l4shmc\\_wait\\_any](#) (l4shmc\_signal\_t \*\*retsignal)  
*Wait on any signal.*
- long [l4shmc\\_wait\\_any\\_try](#) (l4shmc\_signal\_t \*\*retsignal)  
*Check whether any waited signal has an event pending.*
- long [l4shmc\\_wait\\_any\\_to](#) ([l4\\_timeout\\_t](#) timeout, l4shmc\_signal\_t \*\*retsignal)  
*Wait for any signal with timeout.*
- long [l4shmc\\_wait\\_signal](#) (l4shmc\_signal\_t \*signal)  
*Wait on a specific signal.*
- long [l4shmc\\_wait\\_signal\\_to](#) (l4shmc\_signal\_t \*signal, [l4\\_timeout\\_t](#) timeout)  
*Wait on a specific signal, with timeout.*
- long [l4shmc\\_wait\\_signal\\_try](#) (l4shmc\_signal\_t \*signal)  
*Check whether a specific signal has an event pending.*
- long [l4shmc\\_wait\\_chunk](#) (l4shmc\_chunk\_t \*chunk)  
*Wait on a specific chunk.*
- long [l4shmc\\_wait\\_chunk\\_to](#) (l4shmc\_chunk\_t \*chunk, [l4\\_timeout\\_t](#) timeout)  
*Check whether a specific chunk has an event pending, with timeout.*
- long [l4shmc\\_wait\\_chunk\\_try](#) (l4shmc\_chunk\_t \*chunk)  
*Check whether a specific chunk has an event pending.*
- long [l4shmc\\_chunk\\_consumed](#) (l4shmc\_chunk\_t \*chunk)



- Mark a chunk as free.*
- long [l4shmc\\_connect\\_chunk\\_signal](#) (l4shmc\_chunk\_t \*chunk, l4shmc\_signal\_t \*signal)
- Connect a signal with a chunk.*
- long [l4shmc\\_is\\_chunk\\_ready](#) (l4shmc\_chunk\_t const \*chunk)
- Check whether data is available.*
- long [l4shmc\\_is\\_chunk\\_clear](#) (l4shmc\_chunk\_t const \*chunk)
- Check whether chunk is free.*
- void \* [l4shmc\\_chunk\\_ptr](#) (l4shmc\_chunk\_t const \*chunk)
- Get data pointer to chunk.*
- long [l4shmc\\_chunk\\_size](#) (l4shmc\_chunk\_t const \*chunk)
- Get current size of a chunk.*
- long [l4shmc\\_chunk\\_capacity](#) (l4shmc\_chunk\_t const \*chunk)
- Get capacity of a chunk.*
- l4shmc\_signal\_t \* [l4shmc\\_chunk\\_signal](#) (l4shmc\_chunk\_t const \*chunk)
- Get the registered signal of a chunk.*
- [l4\\_cap\\_idx\\_t](#) [l4shmc\\_signal\\_cap](#) (l4shmc\_signal\_t const \*signal)
- Get the signal capability of a signal.*
- long [l4shmc\\_check\\_magic](#) (l4shmc\_chunk\_t const \*chunk)
- Check magic value of a chunk.*
- long [l4shmc\\_area\\_size](#) (l4shmc\_area\_t const \*shmarea)
- Get size of shared memory area.*
- long [l4shmc\\_area\\_size\\_free](#) (l4shmc\_area\_t const \*shmarea)
- Get free size of shared memory area.*
- long [l4shmc\\_area\\_overhead](#) (void)
- Get memory overhead per area that is not available for chunks.*
- long [l4shmc\\_chunk\\_overhead](#) (void)
- Get memory overhead required in addition to the chunk capacity for adding one chunk.*

## 16.419.1 Detailed Description

Shared memory library header file.

Definition in file [shmc.h](#).

## 16.420 shmc.h

[Go to the documentation of this file.](#)

```

00001
00005 /*
00006  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00007  *      Björn Döbel <doebel@os.inf.tu-dresden.de>
00008  *      economic rights: Technische Universität Dresden (Germany)
00009  * This file is part of TUD:OS and distributed under the terms of the
00010  * GNU Lesser General Public License 2.1.
00011  * Please see the COPYING-LGPL-2.1 file for details.
00012  */
00013 #pragma once
00014
00015 #include <l4/sys/compiler.h>
00016 #include <l4/sys/linkage.h>
00017 #include <l4/sys/types.h>
00018 #include <l4/sys/err.h>
00019
00069
00070 #define __INCLUDED_FROM_L4SHMC_H__
00071 #include <l4/shmc/types.h>

```

```
00072
00073 L4_BEGIN_DECLS
00074
00087 L4_CV long
00088 l4shmc_create(char const *shmc_name);
00089
00111 L4_CV long
00112 l4shmc_attach(char const *shmc_name, l4shmc_area_t *shmarea);
00113
00122 L4_CV long
00123 l4shmc_get_client_nr(l4shmc_area_t const *shmarea);
00124
00137 L4_CV long
00138 l4shmc_mark_client_initialized(l4shmc_area_t *shmarea);
00139
00152 L4_CV long
00153 l4shmc_get_initialized_clients(l4shmc_area_t *shmarea, l4_umword_t *bitmask);
00154
00167 L4_CV long
00168 l4shmc_add_chunk(l4shmc_area_t *shmarea, char const *chunk_name,
00169                 l4_umword_t chunk_capacity, l4shmc_chunk_t *chunk);
00170
00182 L4_CV long
00183 l4shmc_add_signal(l4shmc_area_t *shmarea, char const *signal_name,
00184                  l4shmc_signal_t *signal);
00185
00195 L4_CV L4_INLINE long
00196 l4shmc_trigger(l4shmc_signal_t *signal);
00197
00207 L4_CV L4_INLINE long
00208 l4shmc_chunk_try_to_take(l4shmc_chunk_t *chunk);
00209
00221 L4_CV L4_INLINE long
00222 l4shmc_chunk_try_to_take_for_writing(l4shmc_chunk_t *chunk);
00223
00238 L4_CV L4_INLINE long
00239 l4shmc_chunk_try_to_take_for_overwriting(l4shmc_chunk_t *chunk);
00240
00250 L4_CV L4_INLINE long
00251 l4shmc_chunk_try_to_take_for_reading(l4shmc_chunk_t *chunk);
00252
00263 L4_CV L4_INLINE long
00264 l4shmc_chunk_ready(l4shmc_chunk_t *chunk, l4_umword_t size);
00265
00276 L4_CV L4_INLINE long
00277 l4shmc_chunk_ready_sig(l4shmc_chunk_t *chunk, l4_umword_t size);
00278
00290 L4_CV L4_INLINE long
00291 l4shmc_get_chunk(l4shmc_area_t *shmarea, char const *chunk_name,
00292                  l4shmc_chunk_t *chunk);
00293
00307 L4_CV long
00308 l4shmc_get_chunk_to(l4shmc_area_t *shmarea, char const *chunk_name,
00309                     l4_umword_t timeout_ms, l4shmc_chunk_t *chunk);
00310
00324 L4_CV long
00325 l4shmc_iterate_chunk(l4shmc_area_t const *shmarea, char const **chunk_name,
00326                      long offs);
00327
00340 L4_CV long
00341 l4shmc_attach_signal(l4shmc_area_t *shmarea, char const *signal_name,
00342                      l4_cap_idx_t thread, l4shmc_signal_t *signal);
00343
00344
00356 L4_CV long
00357 l4shmc_get_signal(l4shmc_area_t *shmarea, char const *signal_name,
00358                  l4shmc_signal_t *signal);
00359
00373 L4_CV long
00374 l4shmc_enable_signal(l4shmc_signal_t *signal);
00375
00389 L4_CV long
00390 l4shmc_enable_chunk(l4shmc_chunk_t *chunk);
00391
00401 L4_CV L4_INLINE long
00402 l4shmc_wait_any(l4shmc_signal_t **retsignal);
00403
00417 L4_CV L4_INLINE long
00418 l4shmc_wait_any_try(l4shmc_signal_t **retsignal);
00419
00434 L4_CV long
00435 l4shmc_wait_any_to(l4_timeout_t timeout, l4shmc_signal_t **retsignal);
00436
00446 L4_CV L4_INLINE long
00447 l4shmc_wait_signal(l4shmc_signal_t *signal);
00448
00459 L4_CV long
```

```

00460 l4shmc_wait_signal_to(l4shmc_signal_t *signal, l4_timeout_t timeout);
00461
00475 L4_CV L4_INLINE long
00476 l4shmc_wait_signal_try(l4shmc_signal_t *signal);
00477
00487 L4_CV L4_INLINE long
00488 l4shmc_wait_chunk(l4shmc_chunk_t *chunk);
00489
00504 L4_CV long
00505 l4shmc_wait_chunk_to(l4shmc_chunk_t *chunk, l4_timeout_t timeout);
00506
00520 L4_CV L4_INLINE long
00521 l4shmc_wait_chunk_try(l4shmc_chunk_t *chunk);
00522
00532 L4_CV L4_INLINE long
00533 l4shmc_chunk_consumed(l4shmc_chunk_t *chunk);
00534
00545 L4_CV long
00546 l4shmc_connect_chunk_signal(l4shmc_chunk_t *chunk, l4shmc_signal_t *signal);
00547
00557 L4_CV L4_INLINE long
00558 l4shmc_is_chunk_ready(l4shmc_chunk_t const *chunk);
00559
00569 L4_CV L4_INLINE long
00570 l4shmc_is_chunk_clear(l4shmc_chunk_t const *chunk);
00571
00580 L4_CV L4_INLINE void *
00581 l4shmc_chunk_ptr(l4shmc_chunk_t const *chunk);
00582
00591 L4_CV L4_INLINE long
00592 l4shmc_chunk_size(l4shmc_chunk_t const *chunk);
00593
00602 L4_CV L4_INLINE long
00603 l4shmc_chunk_capacity(l4shmc_chunk_t const *chunk);
00604
00614 L4_CV L4_INLINE l4shmc_signal_t *
00615 l4shmc_chunk_signal(l4shmc_chunk_t const *chunk);
00616
00625 L4_CV L4_INLINE l4_cap_idx_t
00626 l4shmc_signal_cap(l4shmc_signal_t const *signal);
00627
00637 L4_CV L4_INLINE long
00638 l4shmc_check_magic(l4shmc_chunk_t const *chunk);
00639
00649 L4_CV long
00650 l4shmc_area_size(l4shmc_area_t const *shmarea);
00651
00661 L4_CV long
00662 l4shmc_area_size_free(l4shmc_area_t const *shmarea);
00663
00670 L4_CV long
00671 l4shmc_area_overhead(void);
00672
00680 L4_CV long
00681 l4shmc_chunk_overhead(void);
00682
00683 #include <l4/shmc/internal.h>
00684
00685 L4_END_DECLS

```

## 16.421 l4/sigma0/sigma0.h File Reference


Sigma0 interface.

```

#include <l4/sys/compiler.h>
#include <l4/sys/types.h>
#include <l4/sys/kip.h>

```

Include dependency graph for sigma0.h:



## Macros

- **#define SIGMA0\_REQ\_MAGIC** ~0xFFUL  
*Request magic.*
- **#define SIGMA0\_REQ\_MASK** ~0xFFUL  
*Request mask.*
- **#define SIGMA0\_REQ\_ID\_MASK** 0xF0  
*ID mask.*
- **#define SIGMA0\_REQ\_ID\_FPAGE\_RAM** 0x60  
*RAM.*
- **#define SIGMA0\_REQ\_ID\_FPAGE\_IOMEM** 0x70  
*I/O memory.*
- **#define SIGMA0\_REQ\_ID\_FPAGE\_IOMEM\_CACHED** 0x80  
*Cached I/O memory.*
- **#define SIGMA0\_REQ\_ID\_FPAGE\_ANY** 0x90  
*Any.*
- **#define SIGMA0\_REQ\_ID\_KIP** 0xA0  
*KIP.*
- **#define SIGMA0\_REQ\_ID\_DEBUG\_DUMP** 0xC0  
*Debug dump.*
- **#define SIGMA0\_REQ\_ID\_COV** 0xE0  
*Trigger cov dump.*
- **#define SIGMA0\_IS\_MAGIC\_REQ**(d1)  
*Check if magic.*
- **#define SIGMA0\_REQ**(x)  
*Construct.*
- **#define SIGMA0\_REQ\_FPAGE\_RAM** ([SIGMA0\\_REQ](#)(FPAGE\_RAM))  
*RAM.*
- **#define SIGMA0\_REQ\_FPAGE\_IOMEM** ([SIGMA0\\_REQ](#)(FPAGE\_IOMEM))  
*I/O memory.*
- **#define SIGMA0\_REQ\_FPAGE\_IOMEM\_CACHED** ([SIGMA0\\_REQ](#)(FPAGE\_IOMEM\_CACHED))  
*Cache I/O memory.*
- **#define SIGMA0\_REQ\_FPAGE\_ANY** ([SIGMA0\\_REQ](#)(FPAGE\_ANY))  
*Any.*

- #define **SIGMA0\_REQ\_KIP** ([SIGMA0\\_REQ](#)(KIP))  
*KIP.*
- #define **SIGMA0\_REQ\_DEBUG\_DUMP** ([SIGMA0\\_REQ](#)(DEBUG\_DUMP))  
*Debug dump.*
- #define **SIGMA0\_REQ\_COV** ([SIGMA0\\_REQ](#)(COV))  
*Cov.*

## Enumerations

- enum [l4sigma0\\_return\\_flags\\_t](#) {  
    [L4SIGMA0\\_OK](#) , [L4SIGMA0\\_NOTALIGNED](#) , [L4SIGMA0\\_IPCERROR](#) , [L4SIGMA0\\_NOFPAGE](#) ,  
    [L4SIGMA0\\_4](#) , [L4SIGMA0\\_5](#) , [L4SIGMA0\\_SMALLERFPAGE](#) }  
*Return flags of libsigma0 functions.*

## Functions

- [L4\\_BEGIN\\_DECLS](#) [l4\\_kernel\\_info\\_t](#) \* [l4sigma0\\_map\\_kip](#) ([l4\\_cap\\_idx\\_t](#) sigma0, void \*addr, unsigned log2↵  
    \_size)  
*Map the kernel info page from sigma0 to addr.*
- int [l4sigma0\\_map\\_mem](#) ([l4\\_cap\\_idx\\_t](#) sigma0, [l4\\_addr\\_t](#) phys, [l4\\_addr\\_t](#) virt, [l4\\_addr\\_t](#) size)  
*Request a memory mapping from sigma0.*
- int [l4sigma0\\_map\\_iomem](#) ([l4\\_cap\\_idx\\_t](#) sigma0, [l4\\_addr\\_t](#) phys, [l4\\_addr\\_t](#) virt, [l4\\_addr\\_t](#) size, int cached)  
*Request IO memory from sigma0.*
- int [l4sigma0\\_map\\_anypage](#) ([l4\\_cap\\_idx\\_t](#) sigma0, [l4\\_addr\\_t](#) map\_area, unsigned log2\_map\_size, [l4\\_addr\\_t](#) \*base, unsigned sz)  
*Request an arbitrary free page of RAM.*
- void [l4sigma0\\_debug\\_dump](#) ([l4\\_cap\\_idx\\_t](#) sigma0)  
*Request sigma0 to dump internal debug information.*
- char const \* [l4sigma0\\_map\\_errstr](#) (int err)  
*Get user readable error messages for the return codes.*

### 16.421.1 Detailed Description

Sigma0 interface.

Definition in file [sigma0.h](#).

## 16.422 sigma0.h

[Go to the documentation of this file.](#)

```

00001
00007 /*
00008  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00009  *             Alexander Warg <warg@os.inf.tu-dresden.de>,
00010  *             Torsten Frenzel <frenzel@os.inf.tu-dresden.de>
00011  *             economic rights: Technische Universität Dresden (Germany)
00012  * License: see LICENSE.spdx (in this directory or the directories above)
00013  */
00014 #ifndef __L4_SIGMA0_SIGMA0_H
00015 #define __L4_SIGMA0_SIGMA0_H
00016
00024
00025 #include <l4/sys/compiler.h>

```

```

00026 #include <l4/sys/types.h>
00027 #include <l4/sys/kip.h>
00028
00035 #undef SIGMA0_REQ_MAGIC
00036 #undef SIGMA0_REQ_MASK
00037
00038 # define SIGMA0_REQ_MAGIC    ~0xFFUL
00039 # define SIGMA0_REQ_MASK    ~0xFFUL
00040
00041 /* Starting with 0x60 allows to detect components which still use the old
00042  * constants (0x00 ... 0x50) */
00043 #define SIGMA0_REQ_ID_MASK    0xF0
00044 #define SIGMA0_REQ_ID_FPAGE_RAM    0x60
00045 #define SIGMA0_REQ_ID_FPAGE_IOMEM    0x70
00046 #define SIGMA0_REQ_ID_FPAGE_IOMEM_CACHED    0x80
00047 #define SIGMA0_REQ_ID_FPAGE_ANY    0x90
00048 #define SIGMA0_REQ_ID_KIP    0xA0
00049 #define SIGMA0_REQ_ID_DEBUG_DUMP    0xC0
00050 #define SIGMA0_REQ_ID_COV    0xE0
00051
00052 #define SIGMA0_IS_MAGIC_REQ(d1) \
00053     ((d1 & SIGMA0_REQ_MASK) == SIGMA0_REQ_MAGIC)
00054
00055 #define SIGMA0_REQ(x) \
00056     (SIGMA0_REQ_MAGIC + SIGMA0_REQ_ID_ ## x)
00057
00058 /* Use these constants in your code! */
00059 #define SIGMA0_REQ_FPAGE_RAM    (SIGMA0_REQ(FPAGE_RAM))
00060 #define SIGMA0_REQ_FPAGE_IOMEM    (SIGMA0_REQ(FPAGE_IOMEM))
00061 #define SIGMA0_REQ_FPAGE_IOMEM_CACHED    (SIGMA0_REQ(FPAGE_IOMEM_CACHED))
00062 #define SIGMA0_REQ_FPAGE_ANY    (SIGMA0_REQ(FPAGE_ANY))
00063 #define SIGMA0_REQ_KIP    (SIGMA0_REQ(KIP))
00064 #define SIGMA0_REQ_DEBUG_DUMP    (SIGMA0_REQ(DEBUG_DUMP))
00065 #define SIGMA0_REQ_COV    (SIGMA0_REQ(COV))
00066
00072
00076 enum l4sigma0_return_flags_t {
00077     L4SIGMA0_OK,
00078     L4SIGMA0_NOTALIGNED,
00079     L4SIGMA0_IPCERROR,
00080     L4SIGMA0_NOFPAGE,
00081     L4SIGMA0_4,
00082     L4SIGMA0_5,
00083     L4SIGMA0_SMALLERFPAGE,
00084 };
00085
00086 L4_BEGIN_DECLS
00087
00097 L4_CV l4_kernel_info_t *
00098 l4sigma0_map_kip(l4_cap_idx_t sigma0, void *addr, unsigned log2_size);
00099
00129 L4_CV int l4sigma0_map_mem(l4_cap_idx_t sigma0,
00130                             l4_addr_t phys, l4_addr_t virt, l4_addr_t size);
00131
00154 L4_CV int l4sigma0_map_iomem(l4_cap_idx_t sigma0, l4_addr_t phys,
00155                               l4_addr_t virt, l4_addr_t size, int cached);
00180 L4_CV int l4sigma0_map_anypage(l4_cap_idx_t sigma0, l4_addr_t map_area,
00181                                unsigned log2_map_size, l4_addr_t *base,
00182                                unsigned sz);
00183
00192 L4_CV void l4sigma0_debug_dump(l4_cap_idx_t sigma0);
00193
00201 L4_INLINE char const *l4sigma0_map_errstr(int err);
00202
00203 L4_CV void l4sigma0_print_cov_data(l4_cap_idx_t pager);
00204
00206
00207
00208 /* Implementations */
00209
00210 L4_INLINE char const *l4sigma0_map_errstr(int err)
00211 {
00212     switch (err)
00213     {
00214         case 0: return "No error";
00215         case -1: return "Phys, virt or size not aligned";
00216         case -2: return "IPC error";
00217         case -3: return "No fpage received";
00218         #ifndef SIGMA0_REQ_MAGIC
00219             case -4: return "Bad physical address (old protocol only)";
00220         #endif
00221         case -6: return "Superpage requested but smaller flexpage received";
00222         case -7: return "Cannot map I/O memory cacheable (old protocol only)";
00223         default: return "Unknown error";
00224     }
00225 }
00226

```

```

00227
00228 L4_END_DECLS
00229
00230 #endif /* ! __L4_SIGMA0_SIGMA0_H */

```

## 16.423 \_\_kernel\_object\_impl.h

```

00001
00006 #pragma once
00007
00008 #include <l4/sys/ipc.h>
00009 #include <l4/sys/kdebug.h>
00010
00011 L4_INLINE l4_msgtag_t
00012 l4_invoke_debugger(l4_cap_idx_t obj, l4_msgtag_t tag, l4_utcb_t *utcb) L4_NOTHROW
00013 {
00014     l4_msgtag_t t2;
00015     unsigned const words = l4_msgtag_words(tag);
00016     l4_msg_regs_t *mr = l4_utcb_mr_u(utcb);
00017
00018     if (l4_is_invalid_cap(obj))
00019         return l4_msgtag(~L4_EINVAL, 0, 0, 0);
00020
00021     if (words + 2 > L4_UTCB_GENERIC_DATA_SIZE)
00022         return l4_msgtag(~L4_EMSTOOLONG, 0, 0, 0);
00023
00024     mr->mr[0] += L4_KDEBUG_GROUP_KOBJ;
00025     mr->mr[words] = L4_ITEM_MAP;
00026     mr->mr[words + 1] = l4_obj_fpage(obj, 0, L4_CAP_FPAGE_RWS).raw;
00027     t2 = l4_msgtag(L4_PROTO_DEBUGGER, words, 1, l4_msgtag_flags(tag));
00028
00029     return l4_ipc_call(L4_BASE_DEBUGGER_CAP, utcb, t2, L4_IPC_NEVER);
00030 }
00031

```

## 16.424 l4/sys/\_\_ktrace-impl.h File Reference


L4 kernel event tracing.

```


#include <l4/sys/types.h>
#include <l4/sys/kdebug.h>

```

Include dependency graph for \_\_ktrace-impl.h:



This graph shows which files directly or indirectly include this file:



## Functions

- [l4\\_umword\\_t fiasco\\_tbuf\\_log](#) (const char \*text)  
*Create new trace-buffer entry with describing <text>.*
- [l4\\_umword\\_t fiasco\\_tbuf\\_log\\_3val](#) (const char \*text, [l4\\_umword\\_t](#) v1, [l4\\_umword\\_t](#) v2, [l4\\_umword\\_t](#) v3)  
*Create new trace-buffer entry with describing <text> and three additional values.*
- void **fiasco\_tbuf\_clear** (void)  
*Clear trace-buffer.*
- void **fiasco\_tbuf\_dump** (void)  
*Dump trace-buffer to kernel console.*
- [l4\\_umword\\_t fiasco\\_tbuf\\_log\\_binary](#) (const unsigned char \*data)  
*Create new trace-buffer entry with binary data.*

## 16.424.1 Detailed Description

[L4](#) kernel event tracing.

Definition in file [\\_\\_ktrace-impl.h](#).

## 16.425 \_\_ktrace-impl.h

[Go to the documentation of this file.](#)

```

00001
00006 /*
00007  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00008  *                Björn Döbel <doebel@os.inf.tu-dresden.de>,
00009  *                Torsten Frenzel <frenzel@os.inf.tu-dresden.de>
00010  *                economic rights: Technische Universität Dresden (Germany)
00011  *
00012  * License: see LICENSE.spdx (in this directory or the directories above)
00013  */
00014 #pragma once
00015
00016 #include <l4/sys/types.h>
00017 #include <l4/sys/kdebug.h>
00018
00019 /*****
00020  *** Implementation
00021  *****/
00022

```



```

00023 L4_INLINE l4_umword_t
00024 fiasco_tbuf_log(const char *text)
00025 {
00026     enum { TBUF_LOG = L4_KDEBUG_GROUP_TRACE + 0x01 };
00027     return l4_error(__l4_kdebug_text(TBUF_LOG, text, __builtin_strlen(text)));
00028 }
00029
00030 L4_INLINE l4_umword_t
00031 fiasco_tbuf_log_3val(const char *text, l4_umword_t v1, l4_umword_t v2,
00032                     l4_umword_t v3)
00033 {
00034     enum { TBUF_LOG_3VAL = L4_KDEBUG_GROUP_TRACE + 0x04 };
00035     return l4_error(__l4_kdebug_3_text(TBUF_LOG_3VAL, text,
00036                                       __builtin_strlen(text), v1, v2, v3));
00037 }
00038
00039 L4_INLINE void
00040 fiasco_tbuf_clear(void)
00041 {
00042     enum { TBUF_CLEAR = L4_KDEBUG_GROUP_TRACE + 0x02 };
00043     __l4_kdebug_op(TBUF_CLEAR);
00044 }
00045
00046 L4_INLINE void
00047 fiasco_tbuf_dump(void)
00048 {
00049     enum { TBUF_DUMP = L4_KDEBUG_GROUP_TRACE + 0x03 };
00050     __l4_kdebug_op(TBUF_DUMP);
00051 }
00052
00053 L4_INLINE l4_umword_t
00054 fiasco_tbuf_log_binary(const unsigned char *data)
00055 {
00056     enum { TBUF_LOG_BIN = L4_KDEBUG_GROUP_TRACE + 0x08 };
00057     return l4_error(__l4_kdebug_text(TBUF_LOG_BIN, (const char *)data, 24));
00058 }
00059

```

## 16.426 \_\_l4\_fpage.h

```

00001
00006 /*
00007  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00008  *      Alexander Warg <warg@os.inf.tu-dresden.de>,
00009  *      Björn Döbel <doebel@os.inf.tu-dresden.de>,
00010  *      Torsten Frenzel <frenzel@os.inf.tu-dresden.de>
00011  *      economic rights: Technische Universität Dresden (Germany)
00012  *
00013  * License: see LICENSE.spdx (in this directory or the directories above)
00014  */
00015 #pragma once
00016
00017 #include <l4/sys/compiler.h>
00018
00043
00048 enum L4_fpage_consts
00049 {
00050     L4_FPAGE_RIGHTS_SHIFT = 0,
00051     L4_FPAGE_TYPE_SHIFT   = 4,
00052     L4_FPAGE_SIZE_SHIFT   = 6,
00053     L4_FPAGE_ADDR_SHIFT   = 12,
00054
00055     L4_FPAGE_RIGHTS_BITS  = 4,
00056     L4_FPAGE_TYPE_BITS   = 2,
00057     L4_FPAGE_SIZE_BITS   = 6,
00058     L4_FPAGE_ADDR_BITS   = L4_MWORD_BITS - L4_FPAGE_ADDR_SHIFT,
00059
00061     L4_FPAGE_RIGHTS_MASK  = ((1UL < L4_FPAGE_RIGHTS_BITS) - 1)
00062                           < L4_FPAGE_RIGHTS_SHIFT,
00063     L4_FPAGE_TYPE_MASK   = ((1UL < L4_FPAGE_TYPE_BITS) - 1)
00064                           < L4_FPAGE_TYPE_SHIFT,
00065     L4_FPAGE_SIZE_MASK   = ((1UL < L4_FPAGE_SIZE_BITS) - 1)
00066                           < L4_FPAGE_SIZE_SHIFT,
00067     L4_FPAGE_ADDR_MASK   = ~0UL < L4_FPAGE_ADDR_SHIFT,
00069     L4_FPAGE_RIGHTS_ALL  = L4_FPAGE_RIGHTS_MASK,
00070 };
00071
00076 typedef union {
00077     l4_umword_t fpage;
00078     l4_umword_t raw;
00079 } l4_fpage_t;
00080
00084 enum

```

```

00085 {
00092     L4_WHOLE_ADDRESS_SPACE = 63
00093 };
00094
00099 typedef struct {
00100     l4_umword_t snd_base;
00101     l4_fpage_t fpage;
00102 } l4_snd_fpage_t;
00103
00104
00118 enum L4_fpage_rights
00119 {
00120     L4_FPAGE_X      = 1,
00121     L4_FPAGE_W      = 2,
00122     L4_FPAGE_RO     = 4,
00123     L4_FPAGE_RW     = L4_FPAGE_RO | L4_FPAGE_W,
00124     L4_FPAGE_RX     = L4_FPAGE_RO | L4_FPAGE_X,
00125     L4_FPAGE_RWX    = L4_FPAGE_RW | L4_FPAGE_X,
00126 };
00127
00148 enum L4_cap_fpage_rights
00149 {
00157     L4_CAP_FPAGE_W      = 0x1,
00169     L4_CAP_FPAGE_S      = 0x2,
00175     L4_CAP_FPAGE_R      = 0x4,
00176     L4_CAP_FPAGE_RO     = 0x4,
00185     L4_CAP_FPAGE_D      = 0x8,
00192     L4_CAP_FPAGE_RW     = L4_CAP_FPAGE_R | L4_CAP_FPAGE_W,
00199     L4_CAP_FPAGE_RS     = L4_CAP_FPAGE_R | L4_CAP_FPAGE_S,
00206     L4_CAP_FPAGE_RWS    = L4_CAP_FPAGE_RW | L4_CAP_FPAGE_S,
00212     L4_CAP_FPAGE_RWSD   = L4_CAP_FPAGE_RWS | L4_CAP_FPAGE_D,
00218     L4_CAP_FPAGE_RWD    = L4_CAP_FPAGE_RW | L4_CAP_FPAGE_D,
00224     L4_CAP_FPAGE_RSD    = L4_CAP_FPAGE_RS | L4_CAP_FPAGE_D,
00225 };
00226
00230 enum L4_fpage_type
00231 {
00232     L4_FPAGE_SPECIAL = 0,
00235     L4_FPAGE_MEMORY  = 1,
00236     L4_FPAGE_IO      = 2,
00237     L4_FPAGE_OBJ     = 3,
00238 };
00239
00243 enum L4_fpage_control
00244 {
00247     L4_FPAGE_CONTROL_OFFSET_SHIFT = 12,
00250     L4_FPAGE_CONTROL_MASK = ~0UL << L4_FPAGE_CONTROL_OFFSET_SHIFT,
00251 };
00252
00264
00266 #define L4_FPAGE_C_REF_CNT      0x00
00267
00269 #define L4_FPAGE_C_NO_REF_CNT  0x10
00270
00272 #define L4_FPAGE_C_OBJ_RIGHT1  0x20
00273
00275 #define L4_FPAGE_C_OBJ_RIGHT2  0x40
00276
00278 #define L4_FPAGE_C_OBJ_RIGHT3  0x80
00279
00281 #define L4_FPAGE_C_OBJ_RIGHTS  0xe0
00282
00288 #define L4_FPAGE_C_IPCGATE_SVR L4_FPAGE_C_OBJ_RIGHT1
00289
00291
00292
00303 enum l4_fpage_cacheability_opt_t
00304 {
00307     L4_FPAGE_CACHE_OPT      = 0x1,
00308
00311     L4_FPAGE_CACHEABLE     = 0x3,
00312
00315     L4_FPAGE_BUFFERABLE    = 0x5,
00316
00319     L4_FPAGE_UNCACHEABLE   = 0x1
00320 };
00321
00322
00326 enum
00327 {
00331     L4_WHOLE_IOADDRESS_SPACE = 16,
00332
00334     L4_IOPORT_MAX             = (1L << L4_WHOLE_IOADDRESS_SPACE)
00335 };
00336
00337
00338

```

```

00353 L4_INLINE l4_fpage_t
00354 l4_fpage(l4_addr_t address, unsigned int order, unsigned char rights) L4_NOTHROW;
00355
00367 L4_INLINE l4_fpage_t
00368 l4_fpage_all(void) L4_NOTHROW;
00369
00376 L4_INLINE l4_fpage_t
00377 l4_fpage_invalid(void) L4_NOTHROW;
00378
00379
00390 L4_INLINE l4_fpage_t
00391 l4_iofpage(unsigned long port, unsigned int order) L4_NOTHROW;
00392
00393
00406 L4_INLINE l4_fpage_t
00407 l4_obj_fpage(l4_cap_idx_t obj, unsigned int order, unsigned char rights) L4_NOTHROW;
00408
00418 L4_INLINE int
00419 l4_is_fpage_writable(l4_fpage_t fp) L4_NOTHROW;
00420
00421
00452
00468 L4_INLINE l4_umword_t
00469 l4_map_control(l4_umword_t spot, unsigned char cache, unsigned grant) L4_NOTHROW;
00470
00484 L4_INLINE l4_umword_t
00485 l4_map_obj_control(l4_umword_t spot, unsigned grant) L4_NOTHROW;
00486
00495 L4_INLINE unsigned
00496 l4_fpage_rights(l4_fpage_t f) L4_NOTHROW;
00497
00506 L4_INLINE unsigned
00507 l4_fpage_type(l4_fpage_t f) L4_NOTHROW;
00508
00519 L4_INLINE unsigned
00520 l4_fpage_size(l4_fpage_t f) L4_NOTHROW;
00521
00532 L4_INLINE unsigned long
00533 l4_fpage_page(l4_fpage_t f) L4_NOTHROW;
00534
00548 L4_INLINE l4_addr_t
00549 l4_fpage_memaddr(l4_fpage_t f) L4_NOTHROW;
00550
00564 L4_INLINE l4_cap_idx_t
00565 l4_fpage_obj(l4_fpage_t f) L4_NOTHROW;
00566
00580 L4_INLINE unsigned long
00581 l4_fpage_ioport(l4_fpage_t f) L4_NOTHROW;
00582
00592 L4_INLINE l4_fpage_t
00593 l4_fpage_set_rights(l4_fpage_t src, unsigned char new_rights) L4_NOTHROW;
00594
00606 L4_INLINE int
00607 l4_fpage_contains(l4_fpage_t fpage, l4_addr_t addr, unsigned order) L4_NOTHROW;
00608
00625 L4_INLINE unsigned char
00626 l4_fpage_max_order(unsigned char order, l4_addr_t addr,
00627                    l4_addr_t min_addr, l4_addr_t max_addr,
00628                    l4_addr_t hotspot L4_DEFAULT_PARAM(0));
00629
00639 L4_INLINE int
00640 l4_is_fpage_valid(l4_fpage_t fp) L4_NOTHROW;
00641
00642 /*****
00643  * Implementations
00644  *****/
00645
00646 L4_INLINE unsigned
00647 l4_fpage_rights(l4_fpage_t f) L4_NOTHROW
00648 {
00649     return (f.raw & L4_FPAGE_RIGHTS_MASK) » L4_FPAGE_RIGHTS_SHIFT;
00650 }
00651
00652 L4_INLINE unsigned
00653 l4_fpage_type(l4_fpage_t f) L4_NOTHROW
00654 {
00655     return (f.raw & L4_FPAGE_TYPE_MASK) » L4_FPAGE_TYPE_SHIFT;
00656 }
00657
00658 L4_INLINE unsigned
00659 l4_fpage_size(l4_fpage_t f) L4_NOTHROW
00660 {
00661     return (f.raw & L4_FPAGE_SIZE_MASK) » L4_FPAGE_SIZE_SHIFT;
00662 }
00663
00664 L4_INLINE unsigned long
00665 l4_fpage_page(l4_fpage_t f) L4_NOTHROW

```

```

00666 {
00667     return (f.raw & L4_FPAGE_ADDR_MASK) » L4_FPAGE_ADDR_SHIFT;
00668 }
00669
00670 L4_INLINE unsigned long
00671 l4_fpage_ioport(l4_fpage_t f) L4_NOTHROW
00672 {
00673     return (f.raw & L4_FPAGE_ADDR_MASK) » L4_FPAGE_ADDR_SHIFT;
00674 }
00675
00676 L4_INLINE l4_addr_t
00677 l4_fpage_memaddr(l4_fpage_t f) L4_NOTHROW
00678 {
00679     return f.raw & L4_FPAGE_ADDR_MASK;
00680 }
00681
00682 L4_INLINE l4_cap_idx_t
00683 l4_fpage_obj(l4_fpage_t f) L4_NOTHROW
00684 {
00685     return f.raw & L4_FPAGE_ADDR_MASK;
00686 }
00687
00688 L4_INLINE l4_fpage_t
00689 __l4_fpage_generic(unsigned long address, unsigned int type,
00690                   unsigned int order, unsigned char rights) L4_NOTHROW;
00691
00692 L4_INLINE l4_fpage_t
00693 __l4_fpage_generic(unsigned long address, unsigned int type,
00694                   unsigned int order, unsigned char rights) L4_NOTHROW
00695 {
00696     l4_fpage_t t;
00697     t.raw = ((rights « L4_FPAGE_RIGHTS_SHIFT) & L4_FPAGE_RIGHTS_MASK)
00698           | ((type « L4_FPAGE_TYPE_SHIFT) & L4_FPAGE_TYPE_MASK)
00699           | ((order « L4_FPAGE_SIZE_SHIFT) & L4_FPAGE_SIZE_MASK)
00700           | ((address & L4_FPAGE_ADDR_MASK));
00701     return t;
00702 }
00703
00704 L4_INLINE l4_fpage_t
00705 l4_fpage_set_rights(l4_fpage_t src, unsigned char new_rights) L4_NOTHROW
00706 {
00707     l4_fpage_t f;
00708     f.raw = ((L4_FPAGE_TYPE_MASK | L4_FPAGE_SIZE_MASK | L4_FPAGE_ADDR_MASK) & src.raw)
00709           | ((new_rights « L4_FPAGE_RIGHTS_SHIFT) & L4_FPAGE_RIGHTS_MASK);
00710     return f;
00711 }
00712
00713 L4_INLINE l4_fpage_t
00714 l4_fpage(l4_addr_t address, unsigned int order, unsigned char rights) L4_NOTHROW
00715 {
00716     return __l4_fpage_generic(address, L4_FPAGE_MEMORY, order, rights);
00717 }
00718
00719 L4_INLINE l4_fpage_t
00720 l4_iofpage(unsigned long port, unsigned int order) L4_NOTHROW
00721 {
00722     return __l4_fpage_generic(port « L4_FPAGE_ADDR_SHIFT, L4_FPAGE_IO, order, L4_FPAGE_RW);
00723 }
00724
00725 L4_INLINE l4_fpage_t
00726 l4_obj_fpage(l4_cap_idx_t obj, unsigned int order, unsigned char rights) L4_NOTHROW
00727 {
00728     static_assert((unsigned long)L4_CAP_SHIFT >= L4_FPAGE_ADDR_SHIFT,
00729                 "Capability index does not fit into fpage.");
00730     return __l4_fpage_generic(obj, L4_FPAGE_OBJ, order, rights);
00731 }
00732
00733 L4_INLINE l4_fpage_t
00734 l4_fpage_all(void) L4_NOTHROW
00735 {
00736     return __l4_fpage_generic(0, L4_FPAGE_SPECIAL, L4_WHOLE_ADDRESS_SPACE, 0);
00737 }
00738
00739 L4_INLINE l4_fpage_t
00740 l4_fpage_invalid(void) L4_NOTHROW
00741 {
00742     return __l4_fpage_generic(0, L4_FPAGE_SPECIAL, 0, 0);
00743 }
00744
00745 L4_INLINE int
00746 l4_is_fpage_writable(l4_fpage_t fp) L4_NOTHROW
00747 {
00748     return l4_fpage_rights(fp) & L4_FPAGE_W;
00749 }
00750
00751 L4_INLINE l4_umword_t

```

```

00754 l4_map_control(l4_umword_t snd_base, unsigned char cache, unsigned grant) L4_NOTHROW
00755 {
00756     return (snd_base & L4_FPAGE_CONTROL_MASK)
00757         | ((l4_umword_t)cache << 4) | L4_ITEM_MAP | grant;
00758 }
00759
00760 L4_INLINE l4_umword_t
00761 l4_map_obj_control(l4_umword_t snd_base, unsigned grant) L4_NOTHROW
00762 {
00763     return l4_map_control(snd_base, 0, grant);
00764 }
00765
00766 L4_INLINE int
00767 l4_fpage_contains(l4_fpage_t fpage, l4_addr_t addr, unsigned log2size) L4_NOTHROW
00768 {
00769     l4_addr_t fa = l4_fpage_memaddr(fpage);
00770     return (fa <= addr)
00771         && (fa + (1UL << l4_fpage_size(fpage)) >= addr + (1UL << log2size));
00772 }
00773
00774 L4_INLINE unsigned char
00775 l4_fpage_max_order(unsigned char order, l4_addr_t addr,
00776                   l4_addr_t min_addr, l4_addr_t max_addr,
00777                   l4_addr_t hotspot)
00778 {
00779     while (order < 30 /* limit to 1GB flexpages */)
00780     {
00781         l4_addr_t mask;
00782         l4_addr_t base = l4_trunc_size(addr, order + 1);
00783         if (base < min_addr)
00784             return order;
00785
00786         if (base + (1UL << (order + 1)) - 1 > max_addr - 1)
00787             return order;
00788
00789         mask = ~(~0UL << (order + 1));
00790         if (hotspot == ~0UL || ((addr ^ hotspot) & mask))
00791             break;
00792
00793         ++order;
00794     }
00795
00796     return order;
00797 }
00798
00799 L4_INLINE int
00800 l4_is_fpage_valid(l4_fpage_t fp) L4_NOTHROW
00801 {
00802     return l4_fpage_type(fp) != L4_FPAGE_SPECIAL || l4_fpage_size(fp) != 0;
00803 }

```

## 16.427 \_\_platform\_control-arm.h

```

00001 /*
00002  * Copyright (C) 2024 Kernkonzept GmbH.
00003  * Author(s): Jan Klötzke <jan.kloetzke@kernkonzept.com>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007 #pragma once
00008
00009 #include <l4/sys/types.h>
00010
00011
00029 L4_INLINE l4_msgtag_t
00030 l4_platform_ctl_set_task_asid(l4_cap_idx_t pfc,
00031                             l4_cap_idx_t task,
00032                             l4_umword_t asid) L4_NOTHROW;
00033
00034
00038 L4_INLINE l4_msgtag_t
00039 l4_platform_ctl_set_task_asid_u(l4_cap_idx_t pfc,
00040                                l4_cap_idx_t task,
00041                                l4_umword_t asid,
00042                                l4_utcb_t *utcb) L4_NOTHROW;
00043
00044 /* IMPLEMENTATION -----*/
00045
00046 L4_INLINE l4_msgtag_t
00047 l4_platform_ctl_set_task_asid_u(l4_cap_idx_t pfc,
00048                                l4_cap_idx_t task,
00049                                l4_umword_t asid,
00050                                l4_utcb_t *utcb) L4_NOTHROW

```

```

00051 {
00052     l4_msg_regs_t *v = l4_utcb_mr_u(utcb);
00053     v->mr[0] = L4_PLATFORM_CTL_SET_TASK_ASID_OP;
00054     v->mr[1] = asid;
00055     v->mr[2] = l4_map_obj_control(0,0);
00056     v->mr[3] = l4_obj_fpage(task, 0, L4_CAP_FPAGE_RWS).raw;
00057     return l4_ipc_call(pfc, utcb, l4_msgtag(L4_PROTO_PLATFORM_CTL, 2, 1, 0),
00058                       L4_IPC_NEVER);
00059 }
00060
00061 L4_INLINE l4_msgtag_t
00062 l4_platform_ctl_set_task_asid(l4_cap_idx_t pfc,
00063                               l4_cap_idx_t task,
00064                               l4_umword_t asid) L4_NOTHROW
00065 {
00066     return l4_platform_ctl_set_task_asid_u(pfc, task, asid, l4_utcb());
00067 }

```

## 16.428 \_\_task-arm.h

```

00001 /*
00002  * (c) 2018 Adam Lackorzynski <adam@l4re.org>
00003  *
00004  * License: see LICENSE.spdx (in this directory or the directories above)
00005  */
00006 #pragma once
00007
00008 #include <l4/sys/types.h>
00009
00013 L4_INLINE l4_msgtag_t
00014 l4_task_vgicc_map_u(l4_cap_idx_t task, l4_fpage_t vgicc_fpage,
00015                    l4_utcb_t *u) L4_NOTHROW;
00016
00028 L4_INLINE l4_msgtag_t
00029 l4_task_vgicc_map(l4_cap_idx_t task, l4_fpage_t vgicc_fpage) L4_NOTHROW;
00030
00031 /* IMPLEMENTATION ----- */
00032
00033 #include <l4/sys/ipc.h>
00034
00035 L4_INLINE l4_msgtag_t
00036 l4_task_vgicc_map_u(l4_cap_idx_t task, l4_fpage_t vgicc_fpage,
00037                    l4_utcb_t *u) L4_NOTHROW
00038 {
00039     l4_msg_regs_t *v = l4_utcb_mr_u(u);
00040     v->mr[0] = L4_TASK_MAP_VGICC_ARM_OP;
00041     v->mr[1] = vgicc_fpage.raw;
00042     return l4_ipc_call(task, u, l4_msgtag(L4_PROTO_TASK, 2, 0, 0), L4_IPC_NEVER);
00043 }
00044
00045 L4_INLINE l4_msgtag_t
00046 l4_task_vgicc_map(l4_cap_idx_t task, l4_fpage_t vgicc_fpage) L4_NOTHROW
00047 {
00048     return l4_task_vgicc_map_u(task, vgicc_fpage, l4_utcb());
00049 }

```

## 16.429 \_\_timeout.h

```

00001
00006 /*
00007  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00008  * Alexander Warg <warg@os.inf.tu-dresden.de>,
00009  * Torsten Frenzel <frenzel@os.inf.tu-dresden.de>
00010  * economic rights: Technische Universität Dresden (Germany)
00011  *
00012  * License: see LICENSE.spdx (in this directory or the directories above)
00013  */
00014 #ifndef L4_SYS_TIMEOUT_H__
00015 #define L4_SYS_TIMEOUT_H__
00016
00017 #include <l4/sys/l4int.h>
00018 #include <l4/sys/compiler.h>
00019
00025
00040 typedef struct l4_timeout_s {
00041     l4_uint16_t t;
00042 } __attribute__((packed)) l4_timeout_s;
00043

```

```

00044
00052 typedef union l4_timeout_t
00053 {
00054     l4_uint32_t raw;
00055     struct
00056     {
00057 #ifdef __BIG_ENDIAN__
00058         l4_timeout_s snd;
00059         l4_timeout_s rcv;
00060 #else
00061         l4_timeout_s rcv;
00062         l4_timeout_s snd;
00063 #endif
00064     } p;
00065 } l4_timeout_t;
00066
00067
00073 #define L4_IPC_TIMEOUT_0 ((l4_timeout_s){0x0400})
00074 #define L4_IPC_TIMEOUT_NEVER ((l4_timeout_s){0})
00075 #define L4_IPC_NEVER_INITIALIZER {0}
00076 #define L4_IPC_NEVER ((l4_timeout_t){0})
00077 #define L4_IPC_RECV_TIMEOUT_0 ((l4_timeout_t){0x00000400})
00078 #define L4_IPC_SEND_TIMEOUT_0 ((l4_timeout_t){0x04000000})
00079 #define L4_IPC_BOTH_TIMEOUT_0 ((l4_timeout_t){0x04000400})
00080
00085 #define L4_TIMEOUT_US_NEVER (~0ULL)
00086
00091 #define L4_TIMEOUT_US_MAX ((1ULL << 41) - 1)
00092
00094
00104 L4_CONSTEXPR L4_INLINE
00105 l4_timeout_s l4_timeout_rel(unsigned man, unsigned exp) L4_NOTHROW;
00106
00107
00117 L4_CONSTEXPR L4_INLINE
00118 l4_timeout_t l4_ipc_timeout(unsigned snd_man, unsigned snd_exp,
00119                             unsigned rcv_man, unsigned rcv_exp) L4_NOTHROW;
00120
00130 L4_CONSTEXPR L4_INLINE
00131 l4_timeout_t l4_timeout(l4_timeout_s snd, l4_timeout_s rcv) L4_NOTHROW;
00132
00140 L4_CONSTEXPR L4_INLINE
00141 void l4_snd_timeout(l4_timeout_s snd, l4_timeout_t *to) L4_NOTHROW;
00142
00150 L4_CONSTEXPR L4_INLINE
00151 void l4_rcv_timeout(l4_timeout_s rcv, l4_timeout_t *to) L4_NOTHROW;
00152
00161 L4_CONSTEXPR L4_INLINE
00162 l4_kernel_clock_t l4_timeout_rel_get(l4_timeout_s to) L4_NOTHROW;
00163
00164
00173 L4_CONSTEXPR L4_INLINE
00174 unsigned l4_timeout_is_absolute(l4_timeout_s to) L4_NOTHROW;
00175
00185 L4_CONSTEXPR L4_INLINE
00186 l4_kernel_clock_t l4_timeout_get(l4_kernel_clock_t cur, l4_timeout_s to) L4_NOTHROW;
00187
00199 L4_CONSTEXPR L4_INLINE
00200 l4_timeout_s l4_timeout_from_us(l4_uint64_t us) L4_NOTHROW;
00201
00202 /*
00203  * Implementation
00204  */
00205
00206 L4_CONSTEXPR L4_INLINE
00207 l4_timeout_t l4_ipc_timeout(unsigned snd_man, unsigned snd_exp,
00208                             unsigned rcv_man, unsigned rcv_exp) L4_NOTHROW
00209 {
00210     l4_uint16_t snd = (snd_man & 0x3ff) | ((snd_exp << 10) & 0x7c00);
00211     l4_uint16_t rcv = (rcv_man & 0x3ff) | ((rcv_exp << 10) & 0x7c00);
00212     return l4_timeout((l4_timeout_s){snd}, (l4_timeout_s){rcv});
00213 }
00214
00215
00216 L4_CONSTEXPR L4_INLINE
00217 l4_timeout_t l4_timeout(l4_timeout_s snd, l4_timeout_s rcv) L4_NOTHROW
00218 {
00219     return (l4_timeout_t){ ((l4_uint32_t){snd.t} << 16) | rcv.t };
00220 }
00221
00222
00223 L4_CONSTEXPR L4_INLINE
00224 void l4_snd_timeout(l4_timeout_s snd, l4_timeout_t *to) L4_NOTHROW
00225 {
00226     to->p.snd = snd;
00227 }
00228

```

```

00229
00230 L4_CONSTEXPR L4_INLINE
00231 void l4_rcv_timeout(l4_timeout_s rcv, l4_timeout_t *to) L4_NOTHROW
00232 {
00233     to->p.rcv = rcv;
00234 }
00235
00236
00237 L4_CONSTEXPR L4_INLINE
00238 l4_timeout_s l4_timeout_rel(unsigned man, unsigned exp) L4_NOTHROW
00239 {
00240     return (l4_timeout_s){(l4_uint16_t)((man & 0x3ff) | ((exp << 10) & 0x7c00))};
00241 }
00242
00243
00244 L4_CONSTEXPR L4_INLINE
00245 l4_kernel_clock_t l4_timeout_rel_get(l4_timeout_s to) L4_NOTHROW
00246 {
00247     if (to.t == 0)
00248         return ~0ULL;
00249     return (l4_kernel_clock_t)(to.t & 0x3ff) << ((to.t > 10) & 0x1f);
00250 }
00251
00252
00253 L4_CONSTEXPR L4_INLINE
00254 unsigned l4_timeout_is_absolute(l4_timeout_s to) L4_NOTHROW
00255 {
00256     return to.t & 0x8000;
00257 }
00258
00259
00260 L4_CONSTEXPR L4_INLINE
00261 l4_kernel_clock_t l4_timeout_get(l4_kernel_clock_t cur, l4_timeout_s to) L4_NOTHROW
00262 {
00263     if (l4_timeout_is_absolute(to))
00264         return 0; /* We cannot retrieve the value ... */
00265     else
00266         return cur + l4_timeout_rel_get(to);
00267 }
00268
00269 L4_CONSTEXPR L4_INLINE
00270 l4_timeout_s l4_timeout_from_us(l4_uint64_t us) L4_NOTHROW
00271 {
00272     if (us == 0)
00273         return L4_IPC_TIMEOUT_0;
00274     else if (us == L4_TIMEOUT_US_NEVER || us > L4_TIMEOUT_US_MAX)
00275         return L4_IPC_TIMEOUT_NEVER;
00276     else
00277     {
00278         /* Here it is certain that at least one bit in 'us' is set. */
00279
00280         enum { m_max = 0x3ff, e_max = 0x1f, }; // max values also serve as mask
00281
00282         l4_uint16_t m = 0; // initialization required by constexpr, optimized away
00283         l4_uint16_t v = 0; // initialization required by constexpr, optimized away
00284         int e = (63 - __builtin_clzll(us)) - 9;
00285         if (e < 0)
00286             e = 0;
00287
00288         /* Here it is certain that '0 <= e <= 31' and '1 <= 2^e <= 2^31':
00289          * L4_TIMEOUT_US_MAX = 2^41-1 = 0x000001fffffffffff => e = 31.
00290          * Note: 2^41-1 (0x000001fffffffffff) > 1023*2^31 (0x00001ff800000000). */
00291
00292         /* Round up to next aligned timeout value to not return too early. */
00293         m = (us + ((1ULL << e) - 1)) >> e;
00294         /* Bounds check */
00295         if (m > m_max)
00296         {
00297             if (e < e_max)
00298             {
00299                 ++e;
00300                 m >>= 1;
00301             }
00302             else
00303                 m = m_max;
00304         }
00305
00306         /* Here it is certain that '1 <= m <= 1023. Consider the following cases:
00307          * o 1 <= us <= 1023: e = 0; 2^e = 1; 1 <= us/1 <= 1023
00308          * o 1024 <= us <= 2047: e = 1; 2^e = 2; 512 <= us/2 <= 1023
00309          * o 2048 <= us <= 4095: e = 2; 2^e = 4; 512 <= us/4 <= 1023
00310          * ...
00311          * o 2^31 <= us <= 2^32-1: e = 22; 512 <= us/2^22 <= 1023
00312          * o 2^40 <= us <= 2^41-1: e = 31; 512 <= us/2^31 <= 1023
00313          *
00314          * Dividing by (1<e) ensures that for all us < 2^41: m < 2^10.
00315          */

```



```

00316      * Maximum possible timeout using this format: L4_TIMEOUT_US_MAX = 2^41-1:
00317      * e = 31, m = 1023 => 2'196'875'771'904 us = 610h 14m 35s.
00318      */
00319
00320      /* Without introducing 'v' we had to type-cast the expression to
00321      * l4_uint16_t. This cannot be avoided by declaring m and e_pow_10 as
00322      * l4_uint16_t due to C++ integer promotion. */
00323      v = (e << 10) | m;
00324      return (l4_timeout_s){v};
00325  }
00326 }
00327
00328 #endif

```

## 16.430 I4/sys/\_\_typeinfo.h File Reference


Type information handling.

```


#include "cxx/types"
#include "cxx/ipc_basics"
#include "cxx/capability.h"

```

Include dependency graph for \_\_typeinfo.h:



This graph shows which files directly or indirectly include this file:



## Data Structures

- struct [L4::Typeid::P\\_dispatch< LIST >](#)  
*Use for protocol based dispatch stage.*
- struct [L4::Typeid::Detail::Rpc\\_end](#)  
*Internal end-of-list marker.*
- struct [L4::Typeid::Detail::\\_Rpc< OPCODE, O, X >](#)  
*Empty list of RPCs.*
- struct [L4::Typeid::Detail::\\_Rpc< OPCODE, O, R, X... >](#)  
*Non-empty list of RPCs.*
- struct [L4::Typeid::Detail::\\_Rpc< OPCODE, O, R, X... >::Rpc< Y >](#)  
*Find the given RPC in the list.*
- struct [L4::Typeid::Detail::\\_Rpc< OPCODE, O, Default\\_op< R > >::Rpc< Y >](#)  
*Find the given RPC in the list.*
- struct [L4::Typeid::Raw\\_ipc< CLASS >](#)  
*RPCs list for passing raw incoming IPC to the server object.*
- struct [L4::Typeid::Rpc< RPCS >](#)  
*Standard list of RPCs of an interface.*
- struct [L4::Typeid::Rpc\\_code< OPCODE\\_TYPE >](#)  
*List of RPCs of an interface using a special opcode type.*
- struct [L4::Typeid::Rpc\\_code< OPCODE\\_TYPE >::F< RPCS >](#)
- struct [L4::Typeid::Rpc\\_nocode< OPERATION >](#)  
*List of RPCs of an interface using a single operation without an opcode.*
- struct [L4::Typeid::Rpc\\_sys< ARG >](#)  
*List of RPCs typically used for kernel interfaces.*
- struct [L4::Type\\_info](#)  
*Dynamic Type Information for [L4Re](#) Interfaces.*
- class [L4::Type\\_info::Demand](#)  
*Data type for expressing the needed receive buffers at the server-side of an interface.*
- struct [L4::Type\\_info::Demand\\_t< CAPS, FLAGS, MEM, PORTS >](#)  
*Template type statically describing demand of receive buffers.*
- struct [L4::Type\\_info::Demand\\_union\\_t< D1, D2 >](#)  
*Template type statically describing the combination of two [Demand](#) object.*
- struct [L4::Kobject\\_typeid< T >](#)  
*Meta object for handling access to type information of Kobjects.*
- struct [L4::Kobject\\_typeid< void >](#)  
*Minimalistic ID for `void` interface.*
- class [L4::Kobject\\_t< Derived, Base, PROTO, S\\_DEMAND >](#)  
*Helper class to create an [L4Re](#) interface class that is derived from a single base class.*
- class [L4::Kobject\\_2t< Derived, Base1, Base2, PROTO, S\\_DEMAND >](#)  
*Helper class to create an [L4Re](#) interface class that is derived from two base classes (see [L4::Kobject\\_t](#)).*
- struct [L4::Kobject\\_3t< Derived, Base1, Base2, Base3, PROTO, S\\_DEMAND >](#)  
*Helper class to create an [L4Re](#) interface class that is derived from three base classes (see [L4::Kobject\\_t](#)).*
- struct [L4::Proto\\_t< P >](#)  
*Data type for defining protocol numbers.*

## Namespaces

- namespace [L4](#)  
*[L4](#) low-level kernel interface.*
- namespace [L4::Typeid](#)  
*Definition of interface data-type helpers.*

## Typedefs

- typedef int **L4::Opcode**  
*Data type for RPC opcodes.*

## Enumerations

- enum : l4\_proto\_t { **L4::PROTO\_ANY** = 0 , **L4::PROTO\_EMPTY** = -19 }

## Functions

- template<typename T>  
**Type\_info** const \* **L4::kobject\_typeid** () noexcept  
*Get the **L4::Type\_info** for the **L4Re** interface given in *T*.*

### 16.430.1 Detailed Description

Type information handling.

Definition in file [\\_\\_typeinfo.h](#).

## 16.431 \_\_typeinfo.h

[Go to the documentation of this file.](#)

```

00001
00005 /*
00006  * Copyright (C) 2014-2017, 2019, 2022-2025 Kernkonzept GmbH.
00007  * Author(s): Alexander Warg <alexander.warg@kernkonzept.com>
00008  */
00009 /*
00010  * (c) 2010 Alexander Warg <warg@os.inf.tu-dresden.de>
00011  *     economic rights: Technische Universität Dresden (Germany)
00012  *
00013  * License: see LICENSE.spdx (in this directory or the directories above)
00014  */
00015 #pragma once
00016 #pragma GCC system_header
00017
00018 #include "cxx/types"
00019 #include "cxx/ipc_basics"
00020 #include "cxx/capability.h"
00021
00022 #if defined(__GXX_RTTI) && !defined(L4_NO_RTTI)
00023 #   include <typeinfo>
00024     typedef std::type_info const *L4_std_type_info_ptr;
00025 #   define L4_KOBJECT_META_RTTI(type) (&typeid(type))
00026     inline char const *L4_kobject_type_name(L4_std_type_info_ptr n) noexcept
00027     { return n ? n->name() : 0; }
00028 #else
00029     typedef void const *L4_std_type_info_ptr;
00030 #   define L4_KOBJECT_META_RTTI(type) (0)
00031     inline char const *L4_kobject_type_name(L4_std_type_info_ptr) noexcept
00032     { return 0; }
00033 #endif
00034
00035 namespace L4 {
00036     typedef int Opcode;
00037     // internal max helpers
00038     namespace __I {
00039         // internal max of A nd B helper
00040         template< unsigned char A, unsigned char B>
00041         struct Max { enum { Res = A > B ? A : B }; };
00042     } // namespace __I
00043

```

```

00044 enum : l4_proto_t
00045 {
00047     PROTO_ANY    = 0,
00049     PROTO_EMPTY  = -19,
00050 };
00051
00058
00066 namespace Typeid {
00071
00072     using namespace L4::Types;
00073
00074     /*****/
00082     template<l4_proto_t P, typename T>
00083     struct Iface
00084     {
00085         typedef Iface type;
00086         typedef T iface_type;
00087         enum { Proto = P };
00088     };
00089
00090
00091     /*****/
00097     struct Iface_list_end
00098     {
00099         typedef Iface_list_end type;
00100         static bool contains(l4_proto_t) noexcept { return false; }
00101     };
00102
00103
00111     template<typename I, typename N = Iface_list_end>
00112     struct Iface_list
00113     {
00114         typedef Iface_list<I, N> type;
00115
00116         typedef typename I::iface_type iface_type;
00117         typedef N Next;
00118
00119         enum { Proto = I::Proto };
00120
00121         static bool contains(l4_proto_t proto) noexcept
00122         { return (proto == Proto) || Next::contains(proto); }
00123     };
00124
00125     // do not insert PROTO_EMPTY interfaces
00126     template<typename I, typename N>
00127     struct Iface_list<Iface<PROTO_EMPTY, I>, N> : N {};
00128
00129     // do not insert 'void' type interfaces
00130     template<l4_proto_t P, typename N>
00131     struct Iface_list<Iface<P, void>, N> : N {};
00132
00133
00134     /*****/
00135     /*
00136     * \internal
00137     * Test if an interface I is in list L
00138     * \tparam I   Interface for lookup
00139     * \tparam L   Iface_list for search
00140     */
00141     template< typename I, typename L >
00142     struct _In_list;
00143
00144     template< typename I >
00145     struct _In_list<I, Iface_list_end> : False {};
00146
00147     template< typename I, typename N >
00148     struct _In_list<I, Iface_list<I, N> > : True {};
00149
00150     template< typename I, typename I2, typename N >
00151     struct _In_list<I, Iface_list<I2, N> > : _In_list<I, typename N::type> {};
00152
00153     template<typename I, typename L>
00154     struct In_list : _In_list<typename I::type, typename L::type> {};
00155
00156
00157     /*****/
00158     /*
00159     * \internal
00160     * Add Helper: add I to interface list L if ADD is true
00161     * \ingroup l4_cxx_ipc_internal
00162     */
00163     template< bool ADD, typename I, typename L>
00164     struct _Iface_list_add;
00165
00166     template< typename I, typename L>
00167     struct _Iface_list_add<false, I, L> : L {};
00168

```

```

00169     template< typename I, typename L>
00170     struct _Iface_list_add<true, I, L> : Iface_list<I, L> {};
00171
00172     /*
00173     * \internal
00174     * Add Helper: add I to interface list L if not already in L.
00175     * \ingroup l4_cxx_ipc_internal
00176     */
00177     template< typename I, typename L >
00178     struct Iface_list_add :
00179         _Iface_list_add<
00180             !In_list<I, typename L::type>::value, I, typename L::type>
00181         {};
00182
00183     /*****
00184     /*
00185     * \internal
00186     * Helper: checking for a conflict between I2 and I2.
00187     * A conflict means I1 and I2 have the same protocol ID but a different
00188     * iface_type.
00189     */
00190     template< typename I1, typename I2 >
00191     struct __Iface_conflict : Bool<I1::Proto != PROTO_EMPTY && I1::Proto == I2::Proto> {};
00192
00193     template< typename I >
00194     struct __Iface_conflict<I, I> : False {};
00195
00196     /*
00197     * \internal
00198     * Helper: checking for a conflict between I and any interface in LIST.
00199     */
00200     template< typename I, typename LIST >
00201     struct _Iface_conflict;
00202
00203     template< typename I >
00204     struct _Iface_conflict<I, Iface_list_end> : False {};
00205
00206     template< typename I, typename I2, typename LIST >
00207     struct _Iface_conflict<I, Iface_list<I2, LIST> > :
00208         Bool<__Iface_conflict<I, I2>::value || _Iface_conflict<I, typename LIST::type>::value>
00209     {};
00210
00211     template< typename I, typename LIST >
00212     struct Iface_conflict : _Iface_conflict<typename I::type, typename LIST::type> {};
00213
00214     /*****
00215     /*
00216     * \internal
00217     * Helper: merge two interface lists
00218     */
00219     template< typename L1, typename L2 >
00220     struct _Merge_list;
00221
00222     template< typename L >
00223     struct _Merge_list<Iface_list_end, L> : L {};
00224
00225     template< typename I, typename L1, typename L2 >
00226     struct _Merge_list<Iface_list<I, L1>, L2> :
00227         _Merge_list<typename L1::type, typename Iface_list_add<I, L2>::type> {};
00228
00229     template<typename L1, typename L2>
00230     struct Merge_list : _Merge_list<typename L1::type, typename L2::type> {};
00231
00232     /*****
00233     /*
00234     * \internal
00235     * check for conflicts among all interfaces in L1 with any interfaces in L2.
00236     */
00237     template< typename L1, typename L2 >
00238     struct _Conflict;
00239
00240     template< typename L >
00241     struct _Conflict<Iface_list_end, L> : False {};
00242
00243     template< typename I, typename L1, typename L2 >
00244     struct _Conflict<Iface_list<I, L1>, L2> :
00245         Bool<Iface_conflict<I, typename L2::type>::value
00246             || _Conflict<typename L1::type, typename L2::type>::value> {};
00247
00248     template< typename L1, typename L2 >
00249     struct Conflict : _Conflict<typename L1::type, typename L2::type> {};
00250
00251     // to be removed -----
00252     // p_dispatch code -- for legacy dispatch -----
00253     /*****
00254     /*
00255     * \internal

```

```

00260     * helper: Dispatch helper for calling server-side p_dispatch() functions.
00261     */
00262     template<typename LIST>
00263     struct _P_dispatch;
00264
00265     // No matching dispatcher found
00266     template<>
00267     struct _P_dispatch<Iface_list_end>
00268     {
00269         template< typename THIS, typename A1, typename A2 >
00270         static int f(THIS *, l4_proto_t, A1, A2 &) noexcept
00271         { return -L4_EBADPROTO; }
00272     };
00273
00274
00275     // call matching p_dispatch() function
00276     template< typename I, typename LIST >
00277     struct _P_dispatch<Iface_list<I, LIST> >
00278     {
00279         // special handling for the meta protocol, to avoid 'using' murx
00280         template< typename THIS, typename A1, typename A2 >
00281         static int _f(THIS self, A1, A2 &a2, True::type)
00282         {
00283             return self->dispatch_meta_request(a2);
00284         }
00285
00286         // normal p_dispatch() dispatching
00287         template< typename THIS, typename A1, typename A2 >
00288         static int _f(THIS self, A1 a1, A2 &a2, False::type)
00289         {
00290             return self->p_dispatch(reinterpret_cast<typename I::iface_type *>(0),
00291                                     a1, a2);
00292         }
00293
00294         // dispatch function with switch for meta protocol
00295         template< typename THIS, typename A1, typename A2 >
00296         static int f(THIS *self, l4_proto_t proto, A1 a1, A2 &a2)
00297         {
00298             if (I::Proto == proto)
00299                 return _f(self, a1, a2,
00300                           Bool<I::Proto == static_cast<l4_proto_t>(L4_PROTO_META)>());
00301
00302             return _P_dispatch<typename LIST::type>::f(self, proto, a1, a2);
00303         }
00304     };
00305
00306     template<typename LIST>
00307     struct P_dispatch : _P_dispatch<typename LIST::type> {};
00308 // end: p_dispatch -----
00309 // end: to be removed -----
00310
00311     template<typename RPC> struct Default_op;
00312
00313     namespace Detail {
00314
00315     struct Rpccs_end
00316     {
00317         typedef void opcode_type;
00318         typedef Rpccs_end rpc;
00319         typedef Rpccs_end type;
00320     };
00321
00322     template<typename O1, typename O2, typename RPCS>
00323     struct _Rpc : _Rpc<typename RPCS::next::rpc, O2, typename RPCS::next>::type {};
00324
00325     template<typename O1, typename O2>
00326     struct _Rpc<O1, O2, Rpccs_end> {};
00327
00328     template<typename OP, typename RPCS>
00329     struct _Rpc<OP, OP, RPCS> : RPCS
00330     {
00331         typedef _Rpc type;
00332     };
00333
00334     template<typename OP, typename RPCS>
00335     struct Rpc : _Rpc<typename RPCS::rpc, OP, RPCS> {};
00336
00337     template<typename T, unsigned CODE>
00338     struct _Get_opcode
00339     {
00340         template<bool, typename> struct Invalid_opcode {};
00341         template<typename X> struct Invalid_opcode<true, X>;
00342     };
00343
00344     private:
00345     template<typename U, U> struct _chk;
00346     template<typename U> static l4_proto_t _opc(_chk<int, U::Opcode> *);
00347     template<typename U> static char _opc(...);

```

```

00351
00352     template<unsigned SZ, typename U>
00353     struct _Opc { enum { value = CODE }; };
00354
00355     template<typename U>
00356     struct _Opc<sizeof(l4_proto_t), U> { enum { value = U::Opcode }; };
00357
00358 public:
00359     enum { value = _Opc<sizeof(_opc<T>)(0), T>::value };
00360     Invalid_opcode<(value < CODE), T> invalid_opcode;
00361 };
00362
00364     template<typename OPCODE, unsigned O, typename ...X>
00365     struct _Rpcs : Rpcs_end {};
00366
00368     template<typename OPCODE, unsigned O, typename R, typename ...X>
00369     struct _Rpcs<OPCODE, O, R, X...>
00370     {
00372         typedef _Rpcs type;
00374         typedef OPCODE opcode_type;
00376         typedef R rpc;
00378         typedef typename _Rpcs<OPCODE, _Get_opcode<R, O>::value + 1, X...>::type next;
00380         enum { Opcode = _Get_opcode<R, O>::value };
00382         template<typename Y> struct Rpc : Typeid::Detail::Rpc<Y, _Rpcs> {};
00383     };
00384
00385     template<typename OPCODE, unsigned O, typename R>
00386     struct _Rpcs<OPCODE, O, Default_op<R> >
00387     {
00389         typedef _Rpcs type;
00391         typedef void opcode_type;
00393         typedef R rpc;
00395         typedef Rpcs_end next;
00397         enum { Opcode = -99 };
00399         template<typename Y> struct Rpc : Typeid::Detail::Rpc<Y, _Rpcs> {};
00400     };
00401
00402 } // namespace Detail
00403
00411     template<typename CLASS>
00412     struct Raw_ipc
00413     {
00414         typedef Raw_ipc type;
00415         typedef Detail::Rpcs_end next;
00416         typedef void opcode_type;
00417     };
00418
00427     template<typename ...RPCS>
00428     struct Rpcs : Detail::_Rpcs<L4::Opcode, 0, RPCS...> {};
00429
00438     template<typename OPCODE_TYPE>
00439     struct Rpcs_code
00440     {
00444         template<typename ...RPCS>
00445         struct F : Detail::_Rpcs<OPCODE_TYPE, 0, RPCS...> {};
00446     };
00447
00453     template<typename OPERATION>
00454     struct Rpc_nocode : Detail::_Rpcs<void, 0, OPERATION> {};
00455
00464     template<typename ...ARG>
00465     struct Rpcs_sys : Detail::_Rpcs<l4_umword_t, 0, ARG...> {};
00466
00467     template<typename CLASS>
00468     struct Rights
00469     {
00470         unsigned rights;
00471         Rights(unsigned rights) noexcept : rights(rights) {}
00472         unsigned operator & (unsigned rhs) const noexcept { return rights & rhs; }
00473     };
00474
00475 } // namespace Typeid
00476
00499 struct L4_EXPORT Type_info
00500 {
00506     class L4_EXPORT Demand
00507     {
00508     private:
00510         static unsigned char max(unsigned char a, unsigned char b) noexcept
00511         { return a > b ? a : b; }
00512
00513     public:
00514         unsigned char caps;
00515         unsigned char flags;
00516         unsigned char mem;
00517         unsigned char ports;
00518

```

```

00526     explicit
00527     Demand(unsigned char caps = 0, unsigned char flags = 0,
00528             unsigned char mem = 0, unsigned char ports = 0) noexcept
00529     : caps(caps), flags(flags), mem(mem), ports(ports) {}
00530
00532     bool no_demand() const noexcept
00533     { return caps == 0 && mem == 0 && ports == 0 && flags == 0; }
00534
00536     Demand operator | (Demand const &rhs) const noexcept
00537     {
00538         return Demand(max(caps, rhs.caps), flags | rhs.flags,
00539                        max(mem, rhs.mem), max(ports, rhs.ports));
00540     }
00541 };
00542
00551 template<unsigned char CAPS = 0, unsigned char FLAGS = 0,
00552          unsigned char MEM = 0, unsigned char PORTS = 0>
00553 struct Demand_t : Demand
00554 {
00555     enum
00556     {
00557         Caps = CAPS,
00558         Flags = FLAGS,
00559         Mem = MEM,
00560         Ports = PORTS
00561     };
00562     Demand_t() noexcept : Demand(CAPS, FLAGS, MEM, PORTS) {}
00563 };
00564
00572 template<typename D1, typename D2>
00573 struct Demand_union_t : Demand_t<__I::Max<D1::Caps, D2::Caps>::Res,
00574                                   D1::Flags | D2::Flags,
00575                                   __I::Max<D1::Mem, D2::Mem>::Res,
00576                                   __I::Max<D1::Ports, D2::Ports>::Res>
00577 {};
00578
00579 L4_std_type_info_ptr _type;
00580 Type_info const *const *_bases;
00581 unsigned _num_bases;
00582 l4_proto_t _proto;
00583
00584 L4_std_type_info_ptr type() const noexcept { return _type; }
00585 Type_info const *base(unsigned idx) const noexcept { return _bases[idx]; }
00586 unsigned num_bases() const noexcept { return _num_bases; }
00587 l4_proto_t proto() const noexcept { return _proto; }
00588 char const *name() const noexcept { return L4_kobject_type_name(type()); }
00589 bool has_proto(l4_proto_t proto) const noexcept
00590 {
00591     if (_proto && _proto == proto)
00592         return true;
00593
00594     if (!proto)
00595         return false;
00596
00597     for (unsigned i = 0; i < _num_bases; ++i)
00598         if (base(i)->has_proto(proto))
00599             return true;
00600
00601     return false;
00602 }
00603 };
00604
00610 template<typename T> struct Kobject_typeid
00611 {
00622     typedef typename T::__Kobject_typeid::Demand Demand;
00623     typedef typename T::__Iface::iface_type Iface;
00624     typedef typename T::__Iface_list Iface_list;
00625
00630     static Type_info const *id() noexcept { return &T::__Kobject_typeid::__m; }
00631
00639     static Type_info::Demand demand() noexcept
00640     { return T::__Kobject_typeid::Demand(); }
00641
00642     // to be removed -----
00643     // p_dispatch -----
00659     template<typename THIS, typename A1, typename A2>
00660     static int proto_dispatch(THIS *self, l4_proto_t proto, A1 a1, A2 &a2)
00661     { return typeid::P_dispatch<typename T::__Iface_list>::f(self, proto, a1, a2); }
00662     // p_dispatch -----
00663     // end: to be removed -----
00664 };
00665
00667 template<> struct Kobject_typeid<void>
00668 {
00669     typedef Type_info::Demand_t<> Demand;
00670 };
00671

```



```

00680 template<typename T>
00681 inline
00682 Type_info const *kobject_typeid() noexcept
00683 { return Kobject_typeid<T>::id(); }
00684
00685 #define L4___GEN_TI(t...)
00690 Type_info const t::__Kobject_typeid::_m =
00691 {
00692     L4_KOBJECT_META_RTTI(Derived),
00693     &t::__Kobject_typeid::_b[0],
00694     sizeof(t::__Kobject_typeid::_b) / sizeof(t::__Kobject_typeid::_b[0]),
00695     PROTO
00696 }
00697
00702 #define L4___GEN_TI_MEMBERS(BASE_DEMAND...)
00703 private:
00704     template< typename T > friend struct Kobject_typeid;
00705 protected:
00706     struct __Kobject_typeid {
00707         typedef Type_info::Demand_union_t<S_DEMAND, BASE_DEMAND> Demand;
00708         static Type_info const *const _b[];
00709         static Type_info const _m;
00710     };
00711 public:
00712     static l4_proto_t const Protocol = PROTO;
00713     typedef L4::Typeid::Rights<Class> Rights;
00714
00743 template<
00744     typename Derived,
00745     typename Base,
00746     l4_proto_t PROTO = PROTO_ANY,
00747     typename S_DEMAND = Type_info::Demand_t<>
00748 >
00749 class Kobject_t : public Base
00750 {
00751 protected:
00753     typedef Derived Class;
00755     typedef Typeid::Iface<PROTO, Derived> __Iface;
00757     typedef Typeid::Merge_list<
00758         Typeid::Iface_list<__Iface>, typename Base::__Iface_list
00759     > __Iface_list;
00760
00762     static void __check_protocols__() noexcept
00763     {
00764         typedef Typeid::Iface_conflict<__Iface, typename Base::__Iface_list> Base_conflict;
00765         static_assert(!Base_conflict::value, "ambiguous protocol ID: protocol also used by Base");
00766     }
00767
00769     L4::Cap<Class> c() const noexcept { return L4::Cap<Class>(this->cap()); }
00770
00771     // Generate the remaining type information
00772     L4___GEN_TI_MEMBERS(typename Base::__Kobject_typeid::Demand)
00773 };
00774
00775
00777 template< typename Derived, typename Base, l4_proto_t PROTO, typename S_DEMAND>
00778 Type_info const *const
00779 Kobject_t<Derived, Base, PROTO, S_DEMAND>::
00780     __Kobject_typeid::_b[] = { &Base::__Kobject_typeid::_m };
00781
00782
00787 template< typename Derived, typename Base, l4_proto_t PROTO, typename S_DEMAND>
00788 L4___GEN_TI(Kobject_t<Derived, Base, PROTO, S_DEMAND>);
00789
00790
00820 template<
00821     typename Derived,
00822     typename Base1,
00823     typename Base2,
00824     l4_proto_t PROTO = PROTO_ANY,
00825     typename S_DEMAND = Type_info::Demand_t<>
00826 >
00827 class Kobject_2t : public Base1, public Base2
00828 {
00829 protected:
00831     typedef Derived Class;
00833     typedef Typeid::Iface<PROTO, Derived> __Iface;
00835     typedef Typeid::Merge_list<
00836         Typeid::Iface_list<__Iface>,
00837         Typeid::Merge_list<
00838             typename Base1::__Iface_list,
00839             typename Base2::__Iface_list
00840         >
00841     > __Iface_list;
00842
00844     static void __check_protocols__() noexcept
00845     {
00846         typedef typename Base1::__Iface_list Base1_proto_list;

```

```

00847     typedef typename Base2::__Iface_list Base2_proto_list;
00848
00849     typedef Typeid::Iface_conflict<__Iface, Base1_proto_list> Base1_conflict;
00850     typedef Typeid::Iface_conflict<__Iface, Base2_proto_list> Base2_conflict;
00851     static_assert(!Base1_conflict::value, "ambiguous protocol ID, also in Base1");
00852     static_assert(!Base2_conflict::value, "ambiguous protocol ID, also in Base2");
00853
00854     typedef Typeid::Conflict<Base1_proto_list, Base2_proto_list> Bases_conflict;
00855     static_assert(!Bases_conflict::value, "ambiguous protocol IDs in base classes");
00856 }
00857
00858 // disambiguate cap()
00859 l4_cap_idx_t cap() const noexcept
00860 { return Base1::cap(); }
00861
00862 L4::Cap<Class> c() const noexcept { return L4::Cap<Class>(this->cap()); }
00863
00864 L4__GEN_TI_MEMBERS(Type_info::Demand_union_t<
00865     typename Base1::__Kobject_typeid::Demand,
00866     typename Base2::__Kobject_typeid::Demand>
00867 )
00868
00869 public:
00870 // Provide non-ambiguous conversion to Kobject
00871 operator Kobject const & () const noexcept
00872 { return *static_cast<Base1 const *>(this); }
00873
00874 // Provide non-ambiguous access of dec_refcnt()
00875 l4_msgtag_t dec_refcnt(l4_mword_t diff, l4_utcb_t *utcb = l4_utcb())
00876 noexcept(noexcept(static_cast<Base1*>(nullptr)->dec_refcnt(diff, utcb)))
00877 { return Base1::dec_refcnt(diff, utcb); }
00878 };
00879
00880
00881
00882 template< typename Derived, typename Base1, typename Base2,
00883     l4_proto_t PROTO, typename S_DEMAND >
00884 Type_info const *const
00885 Kobject_2t<Derived, Base1, Base2, PROTO, S_DEMAND>::__Kobject_typeid::b[] =
00886 {
00887     &Base1::__Kobject_typeid::_m,
00888     &Base2::__Kobject_typeid::_m
00889 };
00890
00891
00892 template< typename Derived, typename Base1, typename Base2,
00893     l4_proto_t PROTO, typename S_DEMAND >
00894 L4__GEN_TI(Kobject_2t<Derived, Base1, Base2, PROTO, S_DEMAND>);
00895
00896
00897
00898 template<
00899     typename Derived,
00900     typename Base1,
00901     typename Base2,
00902     typename Base3,
00903     l4_proto_t PROTO = PROTO_ANY,
00904     typename S_DEMAND = Type_info::Demand_t<>
00905 >
00906 struct Kobject_3t : Base1, Base2, Base3
00907 {
00908 protected:
00909     typedef Derived Class;
00910     typedef Typeid::Iface<PROTO, Derived> __Iface;
00911     typedef Typeid::Merge_list<
00912         Typeid::Iface_list<__Iface>,
00913         Typeid::Merge_list<
00914             typename Base1::__Iface_list,
00915             Typeid::Merge_list<
00916                 typename Base2::__Iface_list,
00917                 typename Base3::__Iface_list
00918             >
00919         >
00920     > __Iface_list;
00921
00922 static void __check_protocols__() noexcept
00923 {
00924     typedef typename Base1::__Iface_list Base1_proto_list;
00925     typedef typename Base2::__Iface_list Base2_proto_list;
00926     typedef typename Base3::__Iface_list Base3_proto_list;
00927
00928     typedef Typeid::Iface_conflict<__Iface, Base1_proto_list> Base1_conflict;
00929     typedef Typeid::Iface_conflict<__Iface, Base2_proto_list> Base2_conflict;
00930     typedef Typeid::Iface_conflict<__Iface, Base3_proto_list> Base3_conflict;
00931
00932     static_assert(!Base1_conflict::value, "ambiguous protocol ID, also in Base1");
00933     static_assert(!Base2_conflict::value, "ambiguous protocol ID, also in Base2");
00934     static_assert(!Base3_conflict::value, "ambiguous protocol ID, also in Base3");
00935 }

```

```

00964     typedef Typeid::Conflict<Base1_proto_list, Base2_proto_list> Conflict_bases12;
00965     typedef Typeid::Conflict<Base1_proto_list, Base3_proto_list> Conflict_bases13;
00966     typedef Typeid::Conflict<Base2_proto_list, Base3_proto_list> Conflict_bases23;
00967
00968     static_assert(!Conflict_bases12::value, "ambiguous protocol IDs in base classes: Base1 and
Base2");
00969     static_assert(!Conflict_bases13::value, "ambiguous protocol IDs in base classes: Base1 and
Base3");
00970     static_assert(!Conflict_bases23::value, "ambiguous protocol IDs in base classes: Base2 and
Base3");
00971 }
00972
00973 // disambiguate cap()
00974 l4_cap_idx_t cap() const noexcept
00975 { return Base1::cap(); }
00976
00977 L4::Cap<Class> c() const noexcept { return L4::Cap<Class>(this->cap()); }
00978
00979 L4__GEN_TI_MEMBERS(Type_info::Demand_union_t<Type_info::Demand_union_t<
00980     typename Base1::__Kobject_typeid::Demand,
00981     typename Base2::__Kobject_typeid::Demand>,
00982     typename Base3::__Kobject_typeid::Demand>
00983 )
00984 )
00985
00986 public:
00987     // Provide non-ambiguous conversion to Kobject
00988     operator Kobject const & () const noexcept
00989     { return *static_cast<Base1 const *>(this); }
00990
00991     // Provide non-ambiguous access of dec_refcnt()
00992     l4_msgtag_t dec_refcnt(l4_mword_t diff, l4_utcb_t *utcb = l4_utcb())
00993     noexcept(noexcept(static_cast<Base1*>(nullptr)->dec_refcnt(diff, utcb)))
00994     { return Base1::dec_refcnt(diff, utcb); }
00995 };
00996
00997
00998 template< typename Derived, typename Base1, typename Base2, typename Base3,
00999     l4_proto_t PROTO, typename S_DEMAND >
01000 Type_info const *const
01001 Kobject_3t<Derived, Base1, Base2, Base3, PROTO, S_DEMAND>::__Kobject_typeid::b[] =
01002 {
01003     &Base1::__Kobject_typeid::_m,
01004     &Base2::__Kobject_typeid::_m,
01005     &Base3::__Kobject_typeid::_m
01006 };
01007
01008 template< typename Derived, typename Base1, typename Base2, typename Base3,
01009     l4_proto_t PROTO, typename S_DEMAND >
01010 L4__GEN_TI(Kobject_3t<Derived, Base1, Base2, Base3, PROTO, S_DEMAND>);
01011
01012 }
01013
01014 #if __cplusplus >= 201103L
01015
01016 namespace L4 {
01017
01018     template< typename ...T >
01019     struct Kobject_demand;
01020
01021     template<>
01022     struct Kobject_demand<> : Type_info::Demand_t<> {};
01023
01024     template<typename T>
01025     struct Kobject_demand<T> : Kobject_typeid<T>::Demand {};
01026
01027     template<typename T1, typename ...T2>
01028     struct Kobject_demand<T1, T2...> :
01029         Type_info::Demand_union_t<typename Kobject_typeid<T1>::Demand,
01030             Kobject_demand<T2...> >
01031     {};
01032
01033 namespace Typeid_xx {
01034
01035     template<typename ...LISTS>
01036     struct Merge_list;
01037
01038     template<typename L>
01039     struct Merge_list<L> : L {};
01040
01041     template<typename L1, typename L2>
01042     struct Merge_list<L1, L2> : Typeid::Merge_list<L1, L2> {};
01043
01044     template<typename L1, typename L2, typename ...LISTS>
01045     struct Merge_list<L1, L2, LISTS...> :
01046         Merge_list<typename Typeid::Merge_list<L1, L2>::type, LISTS...> {};
01047
01048     template< typename I, typename ...LIST >

```

```

01061 struct Iface_conflict;
01062
01063 template< typename I >
01064 struct Iface_conflict<I> : Typeid::False {};
01065
01066 template< typename I, typename L, typename ...LIST >
01067 struct Iface_conflict<I, L, LIST...> :
01068     Typeid::Bool<Typeid::Iface_conflict<typename I::type, typename L::type>::value
01069         || Iface_conflict<I, LIST...>::value>
01070 {};
01071
01072 template< typename ...LIST >
01073 struct Conflict;
01074
01075 template< typename L >
01076 struct Conflict<L> : Typeid::False {};
01077
01078 template< typename L1, typename L2, typename ...LIST >
01079 struct Conflict<L1, L2, LIST...> :
01080     Typeid::Bool<Typeid::Conflict<typename L1::type, typename L2::type>::value
01081         || Conflict<L1, LIST...>::value
01082         || Conflict<L2, LIST...>::value>
01083 {};
01084
01085 template< typename T >
01086 struct Is_demand
01087 {
01088     static l4_proto_t test(Type_info::Demand const *);
01089     static char test(...);
01090     enum { value = sizeof(test(static_cast<T*>(nullptr))) == sizeof(l4_proto_t) };
01091 };
01092
01093 template< typename T, typename ... >
01094 struct First : T { typedef T type; };
01095 } // Typeid
01096
01102 template< typename Derived, l4_proto_t PROTO, typename S_DEMAND, typename ...BASES>
01103 struct __Kobject_base : BASES...
01104 {
01105 protected:
01106     typedef Derived Class;
01107     typedef Typeid::Iface<PROTO, Derived> __Iface;
01108     typedef Typeid_xx::Merge_list<
01109         Typeid::Iface_list<__Iface>,
01110         typename BASES::__Iface_list...
01111     > __Iface_list;
01112
01113     static void __check_protocols__() noexcept
01114     {
01115         typedef Typeid_xx::Iface_conflict<__Iface, typename BASES::__Iface_list...> Conflict;
01116         static_assert(!Conflict::value, "ambiguous protocol ID, protocol also used in base class");
01117
01118         typedef Typeid_xx::Conflict<typename BASES::__Iface_list...> Base_conflict;
01119         static_assert(!Base_conflict::value, "ambiguous protocol IDs in base classes");
01120     }
01121
01122     // disambiguate cap()
01123     l4_cap_idx_t cap() const noexcept
01124     { return Typeid_xx::First<BASES...>::type::cap(); }
01125
01126     L4::Cap<Class> c() const noexcept { return L4::Cap<Class>(this->cap()); }
01127
01128     L4__GEN_TI_MEMBERS(Kobject_demand<BASES...>)
01129
01130 private:
01131     // This function returns the first base class (used below)
01132     template<typename B1, typename ...> struct Base1 { typedef B1 type; };
01133
01134 public:
01135     // Provide non-ambiguous conversion to Kobject
01136     operator Kobject const & () const noexcept
01137     { return *static_cast<typename Base1<BASES...>::type const *>(this); }
01138
01139     // Provide non-ambiguous access of dec_refcnt()
01140     l4_msgtag_t dec_refcnt(l4_mword_t diff, l4_utcb_t *utcb = l4_utcb())
01141     noexcept(noexcept(static_cast<typename Base1<BASES...>::type *>(nullptr)
01142         ->dec_refcnt(diff, utcb)))
01143     { return Base1<BASES...>::type::dec_refcnt(diff, utcb); }
01144 };
01145
01147 template< typename Derived, l4_proto_t PROTO, typename S_DEMAND, typename ...BASES>
01148 Type_info const *const
01149 __Kobject_base<Derived, PROTO, S_DEMAND, BASES...>::__Kobject_typeid::b[] =
01150 {
01151     (&BASES::__Kobject_typeid::m)...
01152 };
01154

```

```

01155 template< typename Derived, l4_proto_t PROTO, typename S_DEMAND, typename ...BASES>
01156 L4____GEN_TI(__Kobject_base<Derived, PROTO, S_DEMAND, BASES...>);
01157
01158
01159 // Test if the there is a Demand argument to Kobject_x
01160 template< typename Derived, l4_proto_t PROTO, bool HAS_DEMAND, typename DEMAND, typename ...ARGS >
01161 struct __Kobject_x_proto;
01162
01163 // YES: pass it to __Kobject_base
01164 template< typename Derived, l4_proto_t PROTO, typename DEMAND, typename ...BASES>
01165 struct __Kobject_x_proto<Derived, PROTO, true, DEMAND, BASES...> :
01166     __Kobject_base<Derived, PROTO, DEMAND, BASES...> {};
01167
01168 // NO: pass it empty Type_info::Demand_t
01169 template< typename Derived, l4_proto_t PROTO, typename B1, typename ...BASES>
01170 struct __Kobject_x_proto<Derived, PROTO, false, B1, BASES...> :
01171     __Kobject_base<Derived, PROTO, Type_info::Demand_t<>, B1, BASES...> {};
01172
01180 template< l4_proto_t P = PROTO_EMPTY >
01181 struct Proto_t {};
01182
01196 template< typename Derived, typename ...ARGS >
01197 struct Kobject_x;
01198
01199 template< typename Derived, typename A, typename ...ARGS >
01200 struct Kobject_x<Derived, A, ARGS...> :
01201     __Kobject_x_proto<Derived, PROTO_ANY, Typeid_xx::Is_demand<A>::value, A, ARGS...>
01202 {};
01203
01204 template< typename Derived, l4_proto_t PROTO, typename A, typename ...ARGS >
01205 struct Kobject_x<Derived, Proto_t<PROTO>, A, ARGS...> :
01206     __Kobject_x_proto<Derived, PROTO, Typeid_xx::Is_demand<A>::value, A, ARGS...>
01207 {};
01208
01209 }
01210 #endif
01211
01212 #undef L4____GEN_TI
01213 #undef L4____GEN_TI_MEMBERS

```

## 16.432 \_\_vcpu-arm.h

```

00001 /*
00002  * (c) 2017 Alexander Warg <alexander.warg@kernkonzept.com>
00003  *
00004  * License: see LICENSE.spdx (in this directory or the directories above)
00005  */
00006 #pragma once
00007
00008 typedef struct l4_arm_vcpu_e_info_t
00009 {
00010     l4_uint8_t version; // must be 0
00011     l4_uint8_t gic_version;
00012     l4_uint8_t _rsvd0[2];
00013     l4_uint32_t features;
00014     l4_uint32_t _rsvd1[14];
00015     l4_umword_t user[8];
00016 } l4_arm_vcpu_e_info_t;
00017
00018 L4_INLINE void *l4_vcpu_e_ptr(void const *vcpu, unsigned id) L4_NOTHROW;
00019
00020 enum L4_vcpu_e_consts
00021 {
00022     L4_VCPU_E_NUM_LR = 4,
00023 };
00024
00025 L4_INLINE l4_arm_vcpu_e_info_t const *
00026 l4_vcpu_e_info(void const *vcpu) L4_NOTHROW;
00027
00028 L4_INLINE l4_umword_t *
00029 l4_vcpu_e_info_user(void *vcpu) L4_NOTHROW;
00030
00031 L4_INLINE l4_umword_t *
00032 l4_vcpu_e_info_user(void *vcpu) L4_NOTHROW
00033 {
00034     return ((l4_arm_vcpu_e_info_t *)l4_vcpu_e_info(vcpu))->user;
00035 }
00036
00037
00045 L4_INLINE l4_uint32_t
00046 l4_vcpu_e_read_32(void const *vcpu, unsigned id) L4_NOTHROW;
00047
00048 L4_INLINE l4_uint32_t

```

```

00049 l4_vcpu_e_read_32(void const *vcpu, unsigned id) L4_NOTHROW
00050 { return *(l4_uint32_t const *)l4_vcpu_e_ptr(vcpu, id); }
00051
00059 L4_INLINE void
00060 l4_vcpu_e_write_32(void *vcpu, unsigned id, l4_uint32_t val) L4_NOTHROW;
00061
00062 L4_INLINE void
00063 l4_vcpu_e_write_32(void *vcpu, unsigned id, l4_uint32_t val) L4_NOTHROW
00064 { *((l4_uint32_t *)l4_vcpu_e_ptr(vcpu, + id)) = val; }
00065
00073 L4_INLINE l4_uint64_t
00074 l4_vcpu_e_read_64(void const *vcpu, unsigned id) L4_NOTHROW;
00075
00076 L4_INLINE l4_uint64_t
00077 l4_vcpu_e_read_64(void const *vcpu, unsigned id) L4_NOTHROW
00078 { return *(l4_uint64_t const *)l4_vcpu_e_ptr(vcpu, id); }
00079
00087 L4_INLINE void
00088 l4_vcpu_e_write_64(void *vcpu, unsigned id, l4_uint64_t val) L4_NOTHROW;
00089
00090 L4_INLINE void
00091 l4_vcpu_e_write_64(void *vcpu, unsigned id, l4_uint64_t val) L4_NOTHROW
00092 { *((l4_uint64_t *)l4_vcpu_e_ptr(vcpu, id)) = val; }
00093
00101 L4_INLINE l4_umword_t
00102 l4_vcpu_e_read(void const *vcpu, unsigned id) L4_NOTHROW;
00103
00104 L4_INLINE l4_umword_t
00105 l4_vcpu_e_read(void const *vcpu, unsigned id) L4_NOTHROW
00106 { return *(l4_umword_t const *)l4_vcpu_e_ptr(vcpu, id); }
00107
00115 L4_INLINE void
00116 l4_vcpu_e_write(void *vcpu, unsigned id, l4_umword_t val) L4_NOTHROW;
00117
00118 L4_INLINE void
00119 l4_vcpu_e_write(void *vcpu, unsigned id, l4_umword_t val) L4_NOTHROW
00120 { *((l4_umword_t *)l4_vcpu_e_ptr(vcpu, id)) = val; }

```

## 16.433 \_\_vm-svm.h

```

00001
00006 /*
00007  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00008  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00009  *      economic rights: Technische Universität Dresden (Germany)
00010  *
00011  * License: see LICENSE.spdx (in this directory or the directories above)
00012  */
00013 #pragma once
00014
00015 #include <l4/sys/types.h>
00016
00022
00023
00028 typedef struct l4_vm_svm_vmcb_control_area
00029 {
00030     l4_uint16_t intercept_rd_crX;
00031     l4_uint16_t intercept_wr_crX;
00032
00033     l4_uint16_t intercept_rd_drX;
00034     l4_uint16_t intercept_wr_drX;
00035
00036     l4_uint32_t intercept_exceptions;
00037
00038     l4_uint32_t intercept_instruction0;
00039     l4_uint32_t intercept_instruction1;
00040
00041     l4_uint8_t _reserved0[40];
00042
00043     l4_uint16_t pause_filter_threshold;
00044     l4_uint16_t pause_filter_count;
00045
00046     l4_uint64_t iopm_base_pa;
00047     l4_uint64_t msrpm_base_pa;
00048     l4_uint64_t tsc_offset;
00049     l4_uint64_t guest_asid_tlb_ctl;
00050     l4_uint64_t interrupt_ctl;
00051     l4_uint64_t interrupt_shadow;
00052     l4_uint64_t exitcode;
00053     l4_uint64_t exitinfo1;
00054     l4_uint64_t exitinfo2;
00055     l4_uint64_t exitintinfo;
00056     l4_uint64_t np_enable;

```

```

00057
00058     14_uint8_t _reserved1[16];
00059
00060     14_uint64_t eventinj;
00061     14_uint64_t n_cr3;
00062     14_uint64_t lbr_virtualization_enable;
00063     14_uint64_t clean_bits;
00064     14_uint64_t n_rip;
00065
00066     14_uint8_t _reserved2[816];
00067 } __attribute__((packed)) 14_vm_svm_vmcb_control_area_t;
00068
00073 typedef struct 14_vm_svm_vmcb_state_save_area_seg
00074 {
00075     14_uint16_t selector;
00076     14_uint16_t attrib;
00077     14_uint32_t limit;
00078     14_uint64_t base;
00079 } __attribute__((packed)) 14_vm_svm_vmcb_state_save_area_seg_t;
00080
00085 typedef struct 14_vm_svm_vmcb_state_save_area
00086 {
00087     struct 14_vm_svm_vmcb_state_save_area_seg es;
00088     struct 14_vm_svm_vmcb_state_save_area_seg cs;
00089     struct 14_vm_svm_vmcb_state_save_area_seg ss;
00090     struct 14_vm_svm_vmcb_state_save_area_seg ds;
00091     struct 14_vm_svm_vmcb_state_save_area_seg fs;
00092     struct 14_vm_svm_vmcb_state_save_area_seg gs;
00093     struct 14_vm_svm_vmcb_state_save_area_seg gdtr;
00094     struct 14_vm_svm_vmcb_state_save_area_seg ldtr;
00095     struct 14_vm_svm_vmcb_state_save_area_seg idtr;
00096     struct 14_vm_svm_vmcb_state_save_area_seg tr;
00097
00098     14_uint8_t _reserved0[43];
00099
00100     14_uint8_t cpl;
00101
00102     14_uint32_t _reserved1;
00103
00104     14_uint64_t efer;
00105
00106     14_uint8_t _reserved2[112];
00107
00108     14_uint64_t cr4;
00109     14_uint64_t cr3;
00110     14_uint64_t cr0;
00111     14_uint64_t dr7;
00112     14_uint64_t dr6;
00113     14_uint64_t rflags;
00114     14_uint64_t rip;
00115
00116     14_uint8_t _reserved3[88];
00117
00118     14_uint64_t rsp;
00119
00120     14_uint8_t _reserved4[24];
00121
00122     14_uint64_t rax;
00123     14_uint64_t star;
00124     14_uint64_t lstar;
00125     14_uint64_t cstar;
00126     14_uint64_t sfmask;
00127     14_uint64_t kernelgsbase;
00128     14_uint64_t sysenter_cs;
00129     14_uint64_t sysenter_esp;
00130     14_uint64_t sysenter_eip;
00131     14_uint64_t cr2;
00132
00133     14_uint8_t _reserved5[32];
00134
00135     14_uint64_t g_pat;
00136     14_uint64_t dbgctl;
00137     14_uint64_t br_from;
00138     14_uint64_t br_to;
00139     14_uint64_t lastexcpfrom;
00140     14_uint64_t last_excpto;
00141
00142     // this field is _NOT_ part of the official VMCB specification
00143     // a (userlevel) VMM needs this for proper FPU state virtualization
00144     14_uint64_t xcr0;
00145
00146     14_uint8_t _reserved6[2400];
00147 } __attribute__((packed)) 14_vm_svm_vmcb_state_save_area_t;
00148
00149
00154 typedef struct 14_vm_svm_vmcb_t
00155 {

```

```

00156     l4_vm_svm_vmcb_control_area_t    control_area;
00157     l4_vm_svm_vmcb_state_save_area_t  state_save_area;
00158 } l4_vm_svm_vmcb_t;

```

## 16.434 \_\_vm-vmx.h

```

00001
00006 /*
00007  * (c) 2010-2013 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00008  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00009  *      economic rights: Technische Universität Dresden (Germany)
00010  *
00011  * License: see LICENSE.spdx (in this directory or the directories above)
00012  */
00013
00014 #pragma once
00015
00016 #include <l4/sys/vcpu.h>
00017
00023
00028 enum l4_vm_vmx_caps_regs
00029 {
00030     L4_VM_VMX_BASIC_REG          = 0,
00031     L4_VM_VMX_TRUE_PINBASED_CTLS_REG = 1,
00032     L4_VM_VMX_TRUE_PROCBASED_CTLS_REG = 2,
00033     L4_VM_VMX_TRUE_EXIT_CTLS_REG   = 3,
00034     L4_VM_VMX_TRUE_ENTRY_CTLS_REG  = 4,
00035     L4_VM_VMX_MISC_REG             = 5,
00036     L4_VM_VMX_CR0_FIXED0_REG       = 6,
00037     L4_VM_VMX_CR0_FIXED1_REG       = 7,
00038     L4_VM_VMX_CR4_FIXED0_REG       = 8,
00039     L4_VM_VMX_CR4_FIXED1_REG       = 9,
00040     L4_VM_VMX_VMCS_ENUM_REG        = 10,
00041     L4_VM_VMX_PROCBASED_CTLS2_REG  = 11,
00042     L4_VM_VMX_EPT_VPID_CAP_REG     = 12,
00043     L4_VM_VMX_NESTED_REVISION      = 13,
00044     L4_VM_VMX_NUM_CAPS_REGS
00045 };
00046
00051 enum l4_vm_vmx_dfl1_regs
00052 {
00053     L4_VM_VMX_PINBASED_CTLS_DFL1_REG = 0,
00054     L4_VM_VMX_PROCBASED_CTLS_DFL1_REG = 1,
00055     L4_VM_VMX_EXIT_CTLS_DFL1_REG     = 2,
00056     L4_VM_VMX_ENTRY_CTLS_DFL1_REG    = 3,
00057     L4_VM_VMX_NUM_DFL1_REGS
00058 };
00059
00069 enum l4_vm_vmx_sw_fields
00070 {
00078     L4_VM_VMX_VMCS_CR2          = 0x6880,
00080     L4_VM_VMX_VMCS_NAT_ARG0     = 0x6882,
00082     L4_VM_VMX_VMCS_NAT_ARG1     = 0x6884,
00084     L4_VM_VMX_VMCS_NAT_ARG2     = 0x6886,
00086     L4_VM_VMX_VMCS_NAT_ARG3     = 0x6888,
00088     L4_VM_VMX_VMCS_XCR0         = 0x2880,
00090     L4_VM_VMX_VMCS_MSR_SYSCALL_MASK = 0x2882,
00092     L4_VM_VMX_VMCS_MSR_LSTAR    = 0x2884,
00094     L4_VM_VMX_VMCS_MSR_CSTAR    = 0x2886,
00096     L4_VM_VMX_VMCS_MSR_TSC_AUX  = 0x2888,
00098     L4_VM_VMX_VMCS_MSR_STAR     = 0x288a,
00100     L4_VM_VMX_VMCS_MSR_KERNEL_GS_BASE = 0x288c,
00101 };
00102
00155 typedef struct l4_vmx_offset_table_t
00156 {
00157     l4_uint8_t offsets[4][4];
00158     l4_uint8_t limits[4][4];
00159     l4_uint8_t index_shifts[4];
00160     l4_uint8_t base_offset;
00161     l4_uint8_t size;
00162
00163     l4_uint8_t reserved[2];
00164 } l4_vmx_offset_table_t;
00165
00170 enum l4_vm_vmx_vmcs_sizes
00171 {
00173     L4_VM_VMX_VMCS_SIZE_VALUES = 2560,
00175     L4_VM_VMX_VMCS_SIZE_DIRTY_BITMAP = 320,
00176 };
00177
00205 typedef struct l4_vm_vmx_vcpu_vmcs_t
00206 {

```



```

00207     l4_uint64_t reserved0;
00208
00209     l4_uint64_t user_data;
00210     l4_uint32_t cr2_index;
00211     l4_uint8_t reserved1[4];
00212
00213     l4_cap_idx_t vmcs;
00214
00215     /*
00216      * Since the capability type size depends on the platform, we add a 32-bit
00217      * padding if necessary.
00218      */
00219
00220     #if L4_MWORD_BITS == 32
00221         l4_uint32_t padding0;
00222     #elif L4_MWORD_BITS == 64
00223         /* No padding needed. */
00224     #else
00225         #error Unsupported machine word size.
00226     #endif
00227
00228     l4_vmx_offset_table_t offset_table;
00229     l4_uint8_t reserved2[120];
00230
00231     l4_uint8_t values[L4_VM_VMX_VMCS_SIZE_VALUES];
00232     l4_uint8_t dirty_bitmap[L4_VM_VMX_VMCS_SIZE_DIRTY_BITMAP];
00233 } l4_vm_vmx_vcpu_vmcs_t;
00234
00239 typedef struct l4_vm_vmx_vcpu_infos_t
00240 {
00242     l4_uint64_t caps[L4_VM_VMX_NUM_CAPS_REGS];
00243
00246     l4_uint32_t dfll[L4_VM_VMX_NUM_DFL1_REGS];
00247 } l4_vm_vmx_vcpu_infos_t;
00248
00267 typedef struct l4_vm_vmx_vcpu_state_t
00268 {
00269     l4_vcpu_state_t vcpu_state;
00270     l4_uint8_t padding0[L4_VCPU_OFFSET_EXT_INFOS - sizeof(l4_vcpu_state_t)];
00271
00272     l4_vm_vmx_vcpu_infos_t infos;
00273     l4_uint8_t padding1[L4_VCPU_OFFSET_EXT_STATE - L4_VCPU_OFFSET_EXT_INFOS
00274                        - sizeof(l4_vm_vmx_vcpu_infos_t)];
00275
00276     l4_vm_vmx_vcpu_vmcs_t vmcs;
00277 } l4_vm_vmx_vcpu_state_t;
00278
00288 L4_INLINE
00289 l4_uint64_t
00290 l4_vm_vmx_get_caps(l4_vm_vmx_vcpu_state_t const *vcpu_state,
00291                   enum L4_vm_vmx_caps_regs caps_reg) L4_NOTHROW;
00292
00303 L4_INLINE
00304 l4_uint32_t
00305 l4_vm_vmx_get_caps_default1(l4_vm_vmx_vcpu_state_t const *vcpu_state,
00306                             enum L4_vm_vmx_dfll_regs dfll_reg) L4_NOTHROW;
00307
00315 L4_INLINE
00316 unsigned
00317 l4_vm_vmx_field_len(unsigned field) L4_NOTHROW;
00318
00326 L4_INLINE
00327 unsigned
00328 l4_vm_vmx_field_order(unsigned field) L4_NOTHROW;
00329
00344 L4_INLINE
00345 void *
00346 l4_vm_vmx_field_ptr(l4_vm_vmx_vcpu_vmcs_t *vmcs, unsigned field) L4_NOTHROW;
00347
00357 L4_INLINE
00358 void
00359 l4_vm_vmx_clear(l4_vm_vmx_vcpu_vmcs_t *vmcs,
00360                l4_vm_vmx_vcpu_vmcs_t *dest_vmcs) L4_NOTHROW;
00361
00371 L4_INLINE
00372 void
00373 l4_vm_vmx_ptr_load(l4_vm_vmx_vcpu_vmcs_t *vmcs,
00374                   l4_vm_vmx_vcpu_vmcs_t *src_vmcs) L4_NOTHROW;
00375
00391 L4_INLINE
00392 l4_uint32_t
00393 l4_vm_vmx_get_cr2_index(l4_vm_vmx_vcpu_vmcs_t const *vmcs) L4_NOTHROW;
00394
00404 L4_INLINE
00405 l4_umword_t
00406 l4_vm_vmx_read_nat(l4_vm_vmx_vcpu_vmcs_t *vmcs, unsigned field) L4_NOTHROW;
00407

```

```

00417 L4_INLINE
00418 l4_uint16_t
00419 l4_vm_vmx_read_16(l4_vm_vmx_vcpu_vmcs_t *vmcs, unsigned field) L4_NOTHROW;
00420
00430 L4_INLINE
00431 l4_uint32_t
00432 l4_vm_vmx_read_32(l4_vm_vmx_vcpu_vmcs_t *vmcs, unsigned field) L4_NOTHROW;
00433
00443 L4_INLINE
00444 l4_uint64_t
00445 l4_vm_vmx_read_64(l4_vm_vmx_vcpu_vmcs_t *vmcs, unsigned field) L4_NOTHROW;
00446
00456 L4_INLINE
00457 l4_uint64_t
00458 l4_vm_vmx_read(l4_vm_vmx_vcpu_vmcs_t *vmcs, unsigned field) L4_NOTHROW;
00459
00468 L4_INLINE
00469 void
00470 l4_vm_vmx_write_nat(l4_vm_vmx_vcpu_vmcs_t *vmcs, unsigned field,
00471                    l4_umword_t val) L4_NOTHROW;
00472
00481 L4_INLINE
00482 void
00483 l4_vm_vmx_write_16(l4_vm_vmx_vcpu_vmcs_t *vmcs, unsigned field,
00484                   l4_uint16_t val) L4_NOTHROW;
00485
00494 L4_INLINE
00495 void
00496 l4_vm_vmx_write_32(l4_vm_vmx_vcpu_vmcs_t *vmcs, unsigned field,
00497                   l4_uint32_t val) L4_NOTHROW;
00498
00507 L4_INLINE
00508 void
00509 l4_vm_vmx_write_64(l4_vm_vmx_vcpu_vmcs_t *vmcs, unsigned field,
00510                   l4_uint64_t val) L4_NOTHROW;
00511
00520 L4_INLINE
00521 void
00522 l4_vm_vmx_write(l4_vm_vmx_vcpu_vmcs_t *vmcs, unsigned field,
00523                l4_uint64_t val) L4_NOTHROW;
00524
00571 L4_INLINE
00572 void
00573 l4_vm_vmx_set_hw_vmcs(l4_vm_vmx_vcpu_vmcs_t *vmcs,
00574                      l4_cap_idx_t vmcs_cap) L4_NOTHROW;
00575
00585 L4_INLINE
00586 l4_cap_idx_t
00587 l4_vm_vmx_get_hw_vmcs(l4_vm_vmx_vcpu_vmcs_t *vmcs) L4_NOTHROW;
00588
00589 /* Implementations */
00590
00591 L4_INLINE
00592 unsigned
00593 l4_vm_vmx_field_len(unsigned field) L4_NOTHROW
00594 {
00595     return 1 << l4_vm_vmx_field_order(field);
00596 }
00597
00598 L4_INLINE
00599 unsigned
00600 l4_vm_vmx_field_order(unsigned field) L4_NOTHROW
00601 {
00602     unsigned size = (field >> 13) & 0x03U;
00603
00604     switch (size)
00605     {
00606         case 0: return 1; /* 16 bits */
00607         case 1: return 3; /* 64 bits */
00608         case 2: return 2; /* 32 bits */
00609         case 3: return (sizeof(l4_umword_t) == 8) ? 3 : 2; /* Natural width */
00610     }
00611
00612     __builtin_trap();
00613 }
00614
00620 L4_INLINE
00621 unsigned
00622 l4_vm_vmx_field_offset(l4_vm_vmx_vcpu_vmcs_t const *vmcs,
00623                       unsigned field) L4_NOTHROW
00624 {
00625     unsigned index = field & 0x3feU;
00626     unsigned size = (field >> 13) & 0x03U;
00627     unsigned group = (field >> 10) & 0x03U;
00628
00629     unsigned shifted_index = index << vmcs->offset_table.index_shifts[size];
00630

```

```

00631     if (shifted_index >= (unsigned)vmcs->offset_table.limits[size][group] * 64)
00632         return ~0U;
00633
00634     return (unsigned)vmcs->offset_table.offsets[size][group] * 64
00635           + shifted_index;
00636 }
00637
00638 L4_INLINE
00639 void *
00640 l4_vm_vmx_field_ptr(l4_vm_vmx_vcpu_vmcs_t *vmcs, unsigned field) L4_NOTHROW
00641 {
00642     unsigned offset = l4_vm_vmx_field_offset(vmcs, field);
00643     if (offset == ~0U)
00644         return 0;
00645
00646     return (void *) (vmcs->values + offset);
00647 }
00648
00649 L4_INLINE
00650 void *
00651 l4_vm_vmx_field_ptr_offset(l4_vm_vmx_vcpu_vmcs_t *vmcs, unsigned field,
00652                           unsigned *offset) L4_NOTHROW
00653 {
00654     *offset = l4_vm_vmx_field_offset(vmcs, field);
00655     if (*offset == ~0U)
00656         return 0;
00657
00658     return (void *) (vmcs->values + *offset);
00659 }
00660
00661 L4_INLINE
00662 void
00663 l4_vm_vmx_offset_dirty(l4_vm_vmx_vcpu_vmcs_t *vmcs,
00664                      unsigned offset) L4_NOTHROW
00665 {
00666     vmcs->dirty_bitmap[offset / 8] |= 1U << (offset % 8);
00667 }
00668
00669 L4_INLINE
00670 void
00671 l4_vm_vmx_copy_values(l4_vm_vmx_vcpu_vmcs_t const *vmcs, l4_uint8_t *_dst,
00672                     l4_uint8_t const *_src) L4_NOTHROW
00673 {
00674     unsigned base_offset = vmcs->offset_table.base_offset * 64;
00675     unsigned size = vmcs->offset_table.size * 64;
00676
00677     void *dst = _dst + base_offset;
00678     void const *src = _src + base_offset;
00679     __builtin_memcpy(dst, src, size);
00680 }
00681
00682 L4_INLINE
00683 void
00684 l4_vm_vmx_clear(l4_vm_vmx_vcpu_vmcs_t *vmcs,
00685               l4_vm_vmx_vcpu_vmcs_t *dest_vmcs) L4_NOTHROW
00686 {
00687     l4_vm_vmx_vcpu_vmcs_t **current_vmcs_ptr
00688     = (l4_vm_vmx_vcpu_vmcs_t **) &vmcs->user_data;
00689
00690     if (*current_vmcs_ptr != dest_vmcs)
00691         return;
00692
00693     l4_vm_vmx_set_hw_vmcs(dest_vmcs, l4_vm_vmx_get_hw_vmcs(vmcs));
00694     l4_vm_vmx_copy_values(vmcs, dest_vmcs->values, vmcs->values);
00695
00696     /* Due to its size, the dirty bitmap is always copied in its entirety. */
00697     __builtin_memcpy(dest_vmcs->dirty_bitmap, vmcs->dirty_bitmap,
00698                   L4_VM_VMX_VMCS_SIZE_DIRTY_BITMAP);
00699
00700     *current_vmcs_ptr = 0;
00701 }
00702
00703 L4_INLINE
00704 void
00705 l4_vm_vmx_ptr_load(l4_vm_vmx_vcpu_vmcs_t *vmcs,
00706                  l4_vm_vmx_vcpu_vmcs_t *src_vmcs) L4_NOTHROW
00707 {
00708     l4_vm_vmx_vcpu_vmcs_t **current_vmcs_ptr
00709     = (l4_vm_vmx_vcpu_vmcs_t **) &vmcs->user_data;
00710
00711     if (*current_vmcs_ptr == src_vmcs)
00712         return;
00713
00714     if (*current_vmcs_ptr && *current_vmcs_ptr != src_vmcs)
00715         l4_vm_vmx_clear(vmcs, *current_vmcs_ptr);
00716
00717     *current_vmcs_ptr = src_vmcs;

```

```

00732
00733     l4_vm_vmx_set_hw_vmcs(vmcs, l4_vm_vmx_get_hw_vmcs(src_vmcs));
00734     l4_vm_vmx_copy_values(vmcs, vmcs->values, src_vmcs->values);
00735
00736     /* Due to its size, the dirty bitmap is always copied in its entirety. */
00737     __builtin_memcpy(vmcs->dirty_bitmap, src_vmcs->dirty_bitmap,
00738         L4_VM_VMX_VMCS_SIZE_DIRTY_BITMAP);
00739 }
00740
00741 L4_INLINE
00742 l4_umword_t
00743 l4_vm_vmx_read_nat(l4_vm_vmx_vcpu_vmcs_t *vmcs, unsigned field) L4_NOTHROW
00744 {
00745     l4_umword_t *ptr = (l4_umword_t *)l4_vm_vmx_field_ptr(vmcs, field);
00746     if (!ptr)
00747         return 0;
00748     return *ptr;
00749 }
00750
00751 L4_INLINE
00752 l4_uint16_t
00753 l4_vm_vmx_read_16(l4_vm_vmx_vcpu_vmcs_t *vmcs, unsigned field) L4_NOTHROW
00754 {
00755     l4_uint16_t *ptr = (l4_uint16_t *)l4_vm_vmx_field_ptr(vmcs, field);
00756     if (!ptr)
00757         return 0;
00758     return *ptr;
00759 }
00760
00761 L4_INLINE
00762 l4_uint32_t
00763 l4_vm_vmx_read_32(l4_vm_vmx_vcpu_vmcs_t *vmcs, unsigned field) L4_NOTHROW
00764 {
00765     l4_uint32_t *ptr = (l4_uint32_t *)l4_vm_vmx_field_ptr(vmcs, field);
00766     if (!ptr)
00767         return 0;
00768     return *ptr;
00769 }
00770
00771 L4_INLINE
00772 l4_uint64_t
00773 l4_vm_vmx_read_64(l4_vm_vmx_vcpu_vmcs_t *vmcs, unsigned field) L4_NOTHROW
00774 {
00775     l4_uint64_t *ptr = (l4_uint64_t *)l4_vm_vmx_field_ptr(vmcs, field);
00776     if (!ptr)
00777         return 0;
00778     return *ptr;
00779 }
00780
00781 L4_INLINE
00782 l4_uint64_t
00783 l4_vm_vmx_read(l4_vm_vmx_vcpu_vmcs_t *vmcs, unsigned field) L4_NOTHROW
00784 {
00785     unsigned size = (field >> 13) & 0x03U;
00786     switch (size)
00787     {
00788         case 0: return l4_vm_vmx_read_16(vmcs, field);
00789         case 1: return l4_vm_vmx_read_64(vmcs, field);
00790         case 2: return l4_vm_vmx_read_32(vmcs, field);
00791         case 3: return l4_vm_vmx_read_nat(vmcs, field);
00792     }
00793     __builtin_trap();
00794 }
00795
00796 L4_INLINE
00797 void
00798 l4_vm_vmx_write_nat(l4_vm_vmx_vcpu_vmcs_t *vmcs, unsigned field,
00799     l4_umword_t val) L4_NOTHROW
00800 {
00801     unsigned offset;
00802     l4_umword_t *ptr
00803         = (l4_umword_t *)l4_vm_vmx_field_ptr_offset(vmcs, field, &offset);
00804     if ((ptr) && (*ptr != val))
00805     {
00806         *ptr = val;
00807         l4_vm_vmx_offset_dirty(vmcs, offset);
00808     }
00809 }
00810
00811 L4_INLINE

```

```

00819 void
00820 l4_vm_vmx_write_16(l4_vm_vmx_vcpu_vmcs_t *vmcs, unsigned field,
00821                  l4_uint16_t val) L4_NOTHROW
00822 {
00823     unsigned offset;
00824     l4_uint16_t *ptr
00825         = (l4_uint16_t *)l4_vm_vmx_field_ptr_offset(vmcs, field, &offset);
00826
00827     if ((ptr) && (*ptr != val))
00828     {
00829         *ptr = val;
00830         l4_vm_vmx_offset_dirty(vmcs, offset);
00831     }
00832 }
00833
00834 L4_INLINE
00835 void
00836 l4_vm_vmx_write_32(l4_vm_vmx_vcpu_vmcs_t *vmcs, unsigned field,
00837                  l4_uint32_t val) L4_NOTHROW
00838 {
00839     unsigned offset;
00840     l4_uint32_t *ptr
00841         = (l4_uint32_t *)l4_vm_vmx_field_ptr_offset(vmcs, field, &offset);
00842
00843     if ((ptr) && (*ptr != val))
00844     {
00845         *ptr = val;
00846         l4_vm_vmx_offset_dirty(vmcs, offset);
00847     }
00848 }
00849
00850 L4_INLINE
00851 void
00852 l4_vm_vmx_write_64(l4_vm_vmx_vcpu_vmcs_t *vmcs, unsigned field,
00853                  l4_uint64_t val) L4_NOTHROW
00854 {
00855     unsigned offset;
00856     l4_uint64_t *ptr
00857         = (l4_uint64_t *)l4_vm_vmx_field_ptr_offset(vmcs, field, &offset);
00858
00859     if ((ptr) && (*ptr != val))
00860     {
00861         *ptr = val;
00862         l4_vm_vmx_offset_dirty(vmcs, offset);
00863     }
00864 }
00865
00866 L4_INLINE
00867 void
00868 l4_vm_vmx_write(l4_vm_vmx_vcpu_vmcs_t *vmcs, unsigned field,
00869                l4_uint64_t val) L4_NOTHROW
00870 {
00871     unsigned size = (field >> 13) & 0x03U;
00872
00873     switch (size)
00874     {
00875         case 0: l4_vm_vmx_write_16(vmcs, field, val); break;
00876         case 1: l4_vm_vmx_write_64(vmcs, field, val); break;
00877         case 2: l4_vm_vmx_write_32(vmcs, field, val); break;
00878         case 3: l4_vm_vmx_write_nat(vmcs, field, val); break;
00879     }
00880 }
00881
00882 L4_INLINE
00883 l4_uint64_t
00884 l4_vm_vmx_get_caps(l4_vm_vmx_vcpu_state_t const *vcpu_state,
00885                  enum L4_vm_vmx_caps_regs caps_reg) L4_NOTHROW
00886 {
00887     return vcpu_state->infos.caps[caps_reg];
00888 }
00889
00890 L4_INLINE
00891 l4_uint32_t
00892 l4_vm_vmx_get_caps_default1(l4_vm_vmx_vcpu_state_t const *vcpu_state,
00893                          enum L4_vm_vmx_dfll_regs dfll_reg) L4_NOTHROW
00894 {
00895     return vcpu_state->infos.dfll[dfll_reg];
00896 }
00897
00898 L4_INLINE
00899 l4_uint32_t
00900 l4_vm_vmx_get_cr2_index(l4_vm_vmx_vcpu_vmcs_t const *vmcs) L4_NOTHROW
00901 {
00902     return vmcs->cr2_index;
00903 }
00904
00905 L4_INLINE

```



## 16.435.1 Detailed Description

ARM secure monitor call functions.

Definition in file [arm\\_smccc](#).

## 16.436 arm\_smccc

[Go to the documentation of this file.](#)

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00002 /*
00003  * Copyright (C) 2018, 2022, 2024 Kernkonzept GmbH.
00004  * Author(s): Sarah Hoffmann <sarah.hoffmann@kernkonzept.com>
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00012 #pragma once
00013
00014 #include <l4/sys/capability>
00015 #include <l4/sys/cxx/ipc_iface>
00016
00017 namespace L4 {
00018
00023 class L4_EXPORT Arm_smccc : public Kobject_0t<Arm_smccc, L4_PROTO_SMCCC>
00024 {
00025 public:
00064     L4_INLINE_RPC(l4_msgtag_t, call,
00065                   (l4_umword_t func, l4_umword_t in0, l4_umword_t in1,
00066                    l4_umword_t in2, l4_umword_t in3, l4_umword_t in4,
00067                    l4_umword_t in5, l4_umword_t *out0, l4_umword_t *out1,
00068                    l4_umword_t *out2, l4_umword_t *out3,
00069                    l4_umword_t client_id));
00070
00071     typedef L4::Typeid::Rpc_nocode<call_t> Rpcs;
00072 };
00073
00074 }
```


## 16.437 l4/sys/arm\_smccc.h File Reference

ARM secure monitor call functions.

```

#include <l4/sys/types.h>
#include <l4/sys/utcb.h>
#include <l4/sys/ipc.h>
```

Include dependency graph for `arm_smccc.h`:



## Functions

- `l4_msgtag_t l4_arm_smccc_call (l4_cap_idx_t pfc, l4_umword_t func, l4_umword_t in0, l4_umword_t in1, l4_umword_t in2, l4_umword_t in3, l4_umword_t in4, l4_umword_t in5, l4_umword_t *out0, l4_umword_t *out1, l4_umword_t *out2, l4_umword_t *out3, l4_umword_t client_id) L4_NOTHROW`

*C interface for calling the ARM secure monitor, see [L4::Arm\\_smccc::call\(\)](#) for the C++ interface.*

### 16.437.1 Detailed Description

ARM secure monitor call functions.

Definition in file [arm\\_smccc.h](#).

### 16.437.2 Function Documentation

#### 16.437.2.1 l4\_arm\_smccc\_call()

```

l4_msgtag_t l4_arm_smccc_call (
    l4_cap_idx_t pfc,
    l4_umword_t func,
    l4_umword_t in0,
    l4_umword_t in1,
    l4_umword_t in2,
    l4_umword_t in3,
    l4_umword_t in4,
    l4_umword_t in5,
    l4_umword_t * out0,
    l4_umword_t * out1,

```



```

14_umword_t * out2,
14_umword_t * out3,
14_umword_t client_id) [inline]

```

C interface for calling the ARM secure monitor, see [L4::Arm\\_smccc::call\(\)](#) for the C++ interface.

### Parameters

	<i>pf</i>	Capability of the SMC kernel object. The input parameters consist of a function identifier, 6 arguments and a client id. Results are returned in 4 output parameters.
	<i>func</i>	Function identifier. <ul style="list-style-type: none"> <li>• Bit 31 has to be set: This marks the call as <i>Fast Call</i>. <i>Yielding Calls</i> (bit 31 unset) are rejected by the kernel.</li> <li>• Bit 30 defines the calling convention:</li> <li>• Bit 30 == 1: 64-bit calling convention.</li> <li>• Bit 30 == 0: 32-bit calling convention.</li> <li>• Bits 24..29 determine the service call ID. The permitted IDs are set in the kernel configuration. By default only service IDs <math>\geq 0x30000000</math> (<i>Trusted Application Calls</i> and <i>Trusted OS Calls</i>) are allowed.</li> </ul>
in	<i>in0</i>	First input parameter.
in	<i>in1</i>	Second input parameter.
in	<i>in2</i>	Third input parameter.
in	<i>in3</i>	Fourth input parameter.
in	<i>in4</i>	Fifth input parameter.
in	<i>in5</i>	Sixth input parameter.
out	<i>out0</i>	First output parameter.
out	<i>out1</i>	Second output parameter.
out	<i>out2</i>	Third output parameter.
out	<i>out3</i>	Fourth output parameter.
in	<i>client_id</i>	Client ID. According to the specification, this value might be ignored by certain functions.


### Return values

-L4_ENOSYS	Either bit 31 of the function call not set or service ID outside the range permitted by kernel configuration.
-L4_EINVAL	Invalid number of parameters.
<0	Other <a href="#">L4</a> error.
0	Success.

Definition at line 42 of file [arm\\_smccc.h](#).

References [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:



## 16.438 arm\_smccc.h

[Go to the documentation of this file.](#)

```

00001 /*
00002  * Copyright (C) 2018, 2022, 2024 Kernkonzept GmbH.
00003  * Author(s): Sarah Hoffmann <sarah.hoffmann@kernkonzept.com>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00011 #pragma once
00012
00013 #include <l4/sys/types.h>
00014 #include <l4/sys/utcb.h>
00015
00016 L4_INLINE l4_msgtag_t
00017 l4_arm_smccc_call(l4_cap_idx_t pfc, l4_umword_t func, l4_umword_t in0,
00018                  l4_umword_t in1, l4_umword_t in2, l4_umword_t in3,
00019                  l4_umword_t in4, l4_umword_t in5, l4_umword_t *out0,
00020                  l4_umword_t *out1, l4_umword_t *out2, l4_umword_t *out3,
00021                  l4_umword_t client_id) L4_NOTHROW;
00022
00023 L4_INLINE l4_msgtag_t
00024 l4_arm_smccc_call_u(l4_cap_idx_t pfc, l4_umword_t func, l4_umword_t in0,
00025                    l4_umword_t in1, l4_umword_t in2, l4_umword_t in3,
00026                    l4_umword_t in4, l4_umword_t in5, l4_umword_t *out0,
00027                    l4_umword_t *out1, l4_umword_t *out2, l4_umword_t *out3,
00028                    l4_umword_t client_id, l4_utcb_t *utcb) L4_NOTHROW;
00029
00030 /* IMPLEMENTATION -----*/
00031
00032 #include <l4/sys/ipc.h>
00033
00041 L4_INLINE l4_msgtag_t
00042 l4_arm_smccc_call(l4_cap_idx_t pfc, l4_umword_t func,
00043                  l4_umword_t in0, l4_umword_t in1,
00044                  l4_umword_t in2, l4_umword_t in3,
00045                  l4_umword_t in4, l4_umword_t in5,
00046                  l4_umword_t *out0, l4_umword_t *out1,
00047                  l4_umword_t *out2, l4_umword_t *out3,
00048                  l4_umword_t client_id) L4_NOTHROW
00049 {
00050     return l4_arm_smccc_call_u(pfc, func, in0, in1, in2, in3, in4, in5,
00051                                out0, out1, out2, out3, client_id, l4_utcb());
00052 }
00053
00054
00055 L4_INLINE l4_msgtag_t
00056 l4_arm_smccc_call_u(l4_cap_idx_t pfc, l4_umword_t func, l4_umword_t in0,
00057                    l4_umword_t in1, l4_umword_t in2, l4_umword_t in3,
00058                    l4_umword_t in4, l4_umword_t in5, l4_umword_t *out0,
00059                    l4_umword_t *out1, l4_umword_t *out2, l4_umword_t *out3,
00060                    l4_umword_t client_id, l4_utcb_t *utcb) L4_NOTHROW
00061 {
00062     l4_msgtag_t ret;
00063     l4_msg_regs_t *v = l4_utcb_mr_u(utcb);
00064     v->mr[0] = func;
00065     v->mr[1] = in0;
00066     v->mr[2] = in1;
00067     v->mr[3] = in2;
00068     v->mr[4] = in3;
00069     v->mr[5] = in4;
00070     v->mr[6] = in5;
00071     v->mr[7] = client_id;
  
```

```

00072
00073     ret = l4_ipc_call(pfc, utcb, l4_msgtag(L4_PROTO_SMCCC, 8, 0, 0),
00074                     L4_IPC_NEVER);
00075
00076     if (l4_error(ret) >= 0)
00077     {
00078         *out0 = v->mr[0];
00079         *out1 = v->mr[1];
00080         *out2 = v->mr[2];
00081         *out3 = v->mr[3];
00082     }
00083
00084     return ret;
00085 }

```

## 16.439 amd64/l4/sys/arch/cache.h File Reference

Cache functions.

### Functions

- int [l4\\_cache\\_clean\\_data](#) (unsigned long start, unsigned long end) [L4\\_NOTHROW](#)  
*Cache clean a range in D-cache; writes back to PoC.*
- int [l4\\_cache\\_flush\\_data](#) (unsigned long start, unsigned long end) [L4\\_NOTHROW](#)  
*Cache flush a range; writes back to PoC.*
- int [l4\\_cache\\_inv\\_data](#) (unsigned long start, unsigned long end) [L4\\_NOTHROW](#)  
*Cache invalidate a range; might write back to PoC.*
- int [l4\\_cache\\_coherent](#) (unsigned long start, unsigned long end) [L4\\_NOTHROW](#)  
*Make memory coherent between I-cache and D-cache; writes back to PoU.*
- int [l4\\_cache\\_dma\\_coherent](#) (unsigned long start, unsigned long end) [L4\\_NOTHROW](#)  
*Make memory coherent for use with external memory; writes back to PoC.*
- int [l4\\_cache\\_dma\\_coherent\\_full](#) (void) [L4\\_NOTHROW](#)  
*Make memory coherent for use with external memory; writes back to PoC.*

### 16.439.1 Detailed Description

Cache functions.

Definition in file [cache.h](#).

## 16.440 cache.h

[Go to the documentation of this file.](#)

```

00001
00002 /*
00003  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>
00004  *     economic rights: Technische Universität Dresden (Germany)
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00008
00009 #ifndef __L4SYS__INCLUDE__ARCH_AMD64__CACHE_H__
00010 #define __L4SYS__INCLUDE__ARCH_AMD64__CACHE_H__
00011
00012 #include <stdint.h>
00013
00014 L4_INLINE int
00015 l4_cache_clean_data(unsigned long start,
00016                    unsigned long end) L4_NOTHROW
00017 {

```

```

00018     (void)start; (void)end;
00019     return 0;
00020 }
00021
00022 L4_INLINE int
00023 l4_cache_flush_data(unsigned long start,
00024                     unsigned long end) L4_NOTHROW
00025 {
00026     (void)start; (void)end;
00027     return 0;
00028 }
00029
00030 L4_INLINE int
00031 l4_cache_inv_data(unsigned long start,
00032                  unsigned long end) L4_NOTHROW
00033 {
00034     (void)start; (void)end;
00035     return 0;
00036 }
00037
00038 L4_INLINE int
00039 l4_cache_coherent(unsigned long start,
00040                  unsigned long end) L4_NOTHROW
00041 {
00042     (void)start; (void)end;
00043     return 0;
00044 }
00045
00046 L4_INLINE int
00047 l4_cache_dma_coherent(unsigned long start,
00048                      unsigned long end) L4_NOTHROW
00049 {
00050     (void)start; (void)end;
00051     return 0;
00052 }
00053
00054 L4_INLINE int
00055 l4_cache_dma_coherent_full(void) L4_NOTHROW
00056 {
00057     return 0;
00058 }
00059
00060 #endif /* ! __L4SYS__INCLUDE__ARCH_AMD64__CACHE_H__ */

```

## 16.441 arm/l4/sys/arch/cache.h File Reference


Cache functions.

```

#include <l4/sys/compiler.h>
#include <l4/sys/syscall_defs.h>

```

Include dependency graph for cache.h:



## Functions

- int [l4\\_cache\\_clean\\_data](#) (unsigned long start, unsigned long end) [L4\\_NOTHROW](#)  
*Cache clean a range in D-cache; writes back to PoC.*
- int [l4\\_cache\\_flush\\_data](#) (unsigned long start, unsigned long end) [L4\\_NOTHROW](#)  
*Cache flush a range; writes back to PoC.*
- int [l4\\_cache\\_inv\\_data](#) (unsigned long start, unsigned long end) [L4\\_NOTHROW](#)  
*Cache invalidate a range; might write back to PoC.*
- int [l4\\_cache\\_coherent](#) (unsigned long start, unsigned long end) [L4\\_NOTHROW](#)  
*Make memory coherent between I-cache and D-cache; writes back to PoU.*
- int [l4\\_cache\\_dma\\_coherent](#) (unsigned long start, unsigned long end) [L4\\_NOTHROW](#)  
*Make memory coherent for use with external memory; writes back to PoC.*
- int [l4\\_cache\\_dma\\_coherent\\_full](#) (void) [L4\\_NOTHROW](#)  
*Make memory coherent for use with external memory; writes back to PoC.*

### 16.441.1 Detailed Description

Cache functions.

Date

2007-11

Author

Adam Lackorzynski [adam@os.inf.tu-dresden.de](mailto:adam@os.inf.tu-dresden.de)

Definition in file [cache.h](#).

## 16.442 cache.h

[Go to the documentation of this file.](#)

```

00001
00009 /*
00010  * (c) 2007-2009 Author(s)
00011  *      economic rights: Technische Universität Dresden (Germany)
00012  *
00013  * License: see LICENSE.spdx (in this directory or the directories above)
00014  */
00015 #ifndef __L4SYS__INCLUDE__ARCH_ARM__CACHE_H__
00016 #define __L4SYS__INCLUDE__ARCH_ARM__CACHE_H__
00017
00018 #include <l4/sys/compiler.h>
00019 #include <l4/sys/syscall_defs.h>
00020
00024 L4_INLINE void
00025 l4_cache_op_arm_call(unsigned long op,
00026                     unsigned long start,
00027                     unsigned long end);
00028
00029 L4_INLINE void
00030 l4_cache_op_arm_call(unsigned long op,
00031                     unsigned long start,
00032                     unsigned long end)
00033 {
00034     register unsigned long _op    __asm__ ("r0") = op;
00035     register unsigned long _start __asm__ ("r1") = start;
00036     register unsigned long _end   __asm__ ("r2") = end;
00037
00038     __asm__ __volatile__

```

```


00039      ("@ l4_cache_op_arm_call(start) \n\t"
00040      "mov      r5, %[sc] \n\t"
00041      "blx      __l4_sys_syscall \n\t"
00042      "@ l4_cache_op_arm_call(end) \n\t"
00043      :
00044      "=r" (_op),
00045      "=r" (_start),
00046      "=r" (_end)
00047      :
00048      [sc] "i" (L4_SYSCALL_MEM_OP),
00049      "0" (_op),
00050      "1" (_start),
00051      "2" (_end)
00052      :
00053      "cc", "memory", "r5", "ip", "lr"
00054      );
00055 }
00056
00057 enum L4_mem_cache_ops
00058 {
00059     L4_MEM_CACHE_OP_CLEAN_DATA      = 0,
00060     L4_MEM_CACHE_OP_FLUSH_DATA      = 1,
00061     L4_MEM_CACHE_OP_INV_DATA        = 2,
00062     L4_MEM_CACHE_OP_COHERENT        = 3,
00063     L4_MEM_CACHE_OP_DMA_COHERENT    = 4,
00064     L4_MEM_CACHE_OP_DMA_COHERENT_FULL = 5,
00065 };
00066
00067 L4_INLINE int
00068 l4_cache_clean_data(unsigned long start,
00069                     unsigned long end) L4_NOTHROW
00070 {
00071     l4_cache_op_arm_call(L4_MEM_CACHE_OP_CLEAN_DATA, start, end);
00072     return 0;
00073 }
00074
00075 L4_INLINE int
00076 l4_cache_flush_data(unsigned long start,
00077                     unsigned long end) L4_NOTHROW
00078 {
00079     l4_cache_op_arm_call(L4_MEM_CACHE_OP_FLUSH_DATA, start, end);
00080     return 0;
00081 }
00082
00083 L4_INLINE int
00084 l4_cache_inv_data(unsigned long start,
00085                   unsigned long end) L4_NOTHROW
00086 {
00087     l4_cache_op_arm_call(L4_MEM_CACHE_OP_INV_DATA, start, end);
00088     return 0;
00089 }
00090
00091 L4_INLINE int
00092 l4_cache_coherent(unsigned long start,
00093                   unsigned long end) L4_NOTHROW
00094 {
00095     l4_cache_op_arm_call(L4_MEM_CACHE_OP_COHERENT, start, end);
00096     return 0;
00097 }
00098
00099 L4_INLINE int
00100 l4_cache_dma_coherent(unsigned long start,
00101                       unsigned long end) L4_NOTHROW
00102 {
00103     l4_cache_op_arm_call(L4_MEM_CACHE_OP_DMA_COHERENT, start, end);
00104     return 0;
00105 }
00106
00107 L4_INLINE int
00108 l4_cache_dma_coherent_full(void) L4_NOTHROW
00109 {
00110     l4_cache_op_arm_call(L4_MEM_CACHE_OP_DMA_COHERENT_FULL, 0, 0);
00111     return 0;
00112 }
00113
00114 #endif /* ! __L4SYS__INCLUDE__ARCH_ARM__CACHE_H__ */

```

## 16.443 arm64/l4/sys/arch/cache.h File Reference

Cache functions.

```
#include <l4/sys/compiler.h>  
Include dependency graph for cache.h:
```



## Functions

- int [l4\\_cache\\_clean\\_data](#) (unsigned long start, unsigned long end) [L4\\_NOTHROW](#)  
*Cache clean a range in D-cache; writes back to PoC.*
- int [l4\\_cache\\_flush\\_data](#) (unsigned long start, unsigned long end) [L4\\_NOTHROW](#)  
*Cache flush a range; writes back to PoC.*
- int [l4\\_cache\\_inv\\_data](#) (unsigned long start, unsigned long end) [L4\\_NOTHROW](#)  
*Cache invalidate a range; might write back to PoC.*
- int [l4\\_cache\\_coherent](#) (unsigned long start, unsigned long end) [L4\\_NOTHROW](#)  
*Make memory coherent between I-cache and D-cache; writes back to PoU.*
- int [l4\\_cache\\_dma\\_coherent](#) (unsigned long start, unsigned long end) [L4\\_NOTHROW](#)  
*Make memory coherent for use with external memory; writes back to PoC.*

### 16.443.1 Detailed Description

Cache functions.

Date

2007-11

Author

Adam Lackorzynski [adam@os.inf.tu-dresden.de](mailto:adam@os.inf.tu-dresden.de)

Definition in file [cache.h](#).

## 16.444 cache.h

[Go to the documentation of this file.](#)

```

00001
00009 /*
00010  * (c) 2007-2009 Author(s)
00011  *     economic rights: Technische Universität Dresden (Germany)
00012  *
00013  * License: see LICENSE.spdx (in this directory or the directories above)
00014  */
00015 #ifndef __L4SYS__INCLUDE__ARCH_ARM__CACHE_H__
00016 #define __L4SYS__INCLUDE__ARCH_ARM__CACHE_H__
00017
00018 #include <l4/sys/compiler.h>
00019
00020 L4_INLINE unsigned long __attribute__((pure, always_inline))
00021 l4_cache_arm_ctr(void);
00022
00023 L4_INLINE unsigned long __attribute__((pure, always_inline))
00024 l4_cache_arm_ctr(void)
00025 {
00026     unsigned long v;
00027     asm ("mrs %0, CTR_EL0" : "=r"(v));
00028     return v;
00029 }
00030
00031 L4_INLINE unsigned __attribute__((pure, always_inline))
00032 l4_cache_dmin_line(void);
00033
00034 L4_INLINE unsigned __attribute__((pure, always_inline))
00035 l4_cache_dmin_line(void)
00036 {
00037     return 4U << ((l4_cache_arm_ctr() >> 16) & 0xf);
00038 }
00039
00040 #define L4_ARM_CACHE_LOOP(op)
00041     unsigned long step;
00042
00043     if (start > end)
00044         __builtin_unreachable();
00045
00046     step = l4_cache_dmin_line();
00047     start &= ~(step - 1);
00048     end = (end + step - 1) & ~(step - 1);
00049     for (; start != end; start += step)
00050         asm volatile (op " ", %0" : : "r"(start) : "memory");
00051     asm volatile ("dsb ish");
00052
00053
00054 L4_INLINE int
00055 l4_cache_clean_data(unsigned long start,
00056                     unsigned long end) L4_NOTHROW
00057 {
00058     L4_ARM_CACHE_LOOP("dc cvac");
00059     return 0;
00060 }
00061
00062 L4_INLINE int
00063 l4_cache_flush_data(unsigned long start,
00064                     unsigned long end) L4_NOTHROW
00065 {
00066     L4_ARM_CACHE_LOOP("dc civac");
00067     return 0;
00068 }
00069
00070 L4_INLINE int
00071 l4_cache_inv_data(unsigned long start,
00072                   unsigned long end) L4_NOTHROW
00073 {
00074     // DC IVAC is always privileged, use DC CIVAC instead
00075     L4_ARM_CACHE_LOOP("dc civac");
00076     return 0;
00077 }
00078
00079 L4_INLINE int
00080 l4_cache_coherent(unsigned long start,
00081                   unsigned long end) L4_NOTHROW
00082 {
00083     L4_ARM_CACHE_LOOP("dc cvau, %0; ic ivau");
00084     asm volatile ("isb");
00085     return 0;
00086 }
00087
00088 L4_INLINE int
00089 l4_cache_dma_coherent(unsigned long start,
```



```

00090             unsigned long end) L4_NOTHROW
00091 {
00092     L4_ARM_CACHE_LOOP("dc civac");
00093     return 0;
00094 }
00095
00096 #undef L4_ARM_CACHE_LOOP
00097
00098 #endif /* ! __L4SYS__INCLUDE__ARCH_ARM__CACHE_H__ */

```

## 16.445 l4/sys/cache.h File Reference


Cache-consistency functions.

```

#include <l4/sys/compiler.h>
#include <l4/sys/arch/cache.h>

```

Include dependency graph for cache.h:



### Functions

- [L4\\_BEGIN\\_DECLS](#) `int l4_cache_clean_data` (unsigned long start, unsigned long end) [L4\\_NOTHROW](#)  
Cache clean a range in D-cache; writes back to PoC.
- `int l4_cache_flush_data` (unsigned long start, unsigned long end) [L4\\_NOTHROW](#)  
Cache flush a range; writes back to PoC.
- `int l4_cache_inv_data` (unsigned long start, unsigned long end) [L4\\_NOTHROW](#)  
Cache invalidate a range; might write back to PoC.
- `int l4_cache_coherent` (unsigned long start, unsigned long end) [L4\\_NOTHROW](#)  
Make memory coherent between I-cache and D-cache; writes back to PoU.
- `int l4_cache_dma_coherent` (unsigned long start, unsigned long end) [L4\\_NOTHROW](#)  
Make memory coherent for use with external memory; writes back to PoC.
- `int l4_cache_dma_coherent_full` (void) [L4\\_NOTHROW](#)  
Make memory coherent for use with external memory; writes back to PoC.

## 16.445.1 Detailed Description

Cache-consistency functions.

### Date

2007-11

### Author

Adam Lackorzynski [adam@os.inf.tu-dresden.de](mailto:adam@os.inf.tu-dresden.de)

Definition in file [cache.h](#).

## 16.446 cache.h

[Go to the documentation of this file.](#)

```

00001
00010 /*
00011  * (c) 2007-2009 Author(s)
00012  *     economic rights: Technische Universität Dresden (Germany)
00013  *
00014  * License: see LICENSE.spdx (in this directory or the directories above)
00015  */
00016
00017 #ifndef __L4SYS__INCLUDE__CACHE_H__
00018 #define __L4SYS__INCLUDE__CACHE_H__
00019
00020 #include <l4/sys/compiler.h>
00021
00036
00037 L4_BEGIN_DECLS
00038
00053 L4_INLINE int
00054 l4_cache_clean_data(unsigned long start,
00055                     unsigned long end) L4_NOTHROW;
00056
00071 L4_INLINE int
00072 l4_cache_flush_data(unsigned long start,
00073                     unsigned long end) L4_NOTHROW;
00074
00093 L4_INLINE int
00094 l4_cache_inv_data(unsigned long start,
00095                   unsigned long end) L4_NOTHROW;
00096
00108 L4_INLINE int
00109 l4_cache_coherent(unsigned long start,
00110                   unsigned long end) L4_NOTHROW;
00111
00123 L4_INLINE int
00124 l4_cache_dma_coherent(unsigned long start,
00125                       unsigned long end) L4_NOTHROW;
00126
00127 #if !defined(ARCH_arm64)
00132 L4_INLINE int
00133 l4_cache_dma_coherent_full(void) L4_NOTHROW;
00134 #endif
00135
00136 L4_END_DECLS
00137
00138 #include <l4/sys/arch/cache.h>
00139
00140 #endif /* ! __L4SYS__INCLUDE__CACHE_H__ */

```

## 16.447 x86/l4/sys/arch/cache.h File Reference

Cache functions.

## Functions

- `int l4_cache_clean_data` (unsigned long start, unsigned long end) [L4\\_NOTHROW](#)  
*Cache clean a range in D-cache; writes back to PoC.*
- `int l4_cache_flush_data` (unsigned long start, unsigned long end) [L4\\_NOTHROW](#)  
*Cache flush a range; writes back to PoC.*
- `int l4_cache_inv_data` (unsigned long start, unsigned long end) [L4\\_NOTHROW](#)  
*Cache invalidate a range; might write back to PoC.*
- `int l4_cache_coherent` (unsigned long start, unsigned long end) [L4\\_NOTHROW](#)  
*Make memory coherent between I-cache and D-cache; writes back to PoU.*
- `int l4_cache_dma_coherent` (unsigned long start, unsigned long end) [L4\\_NOTHROW](#)  
*Make memory coherent for use with external memory; writes back to PoC.*
- `int l4_cache_dma_coherent_full` (void) [L4\\_NOTHROW](#)  
*Make memory coherent for use with external memory; writes back to PoC.*

### 16.447.1 Detailed Description

Cache functions.

Definition in file [cache.h](#).

## 16.448 cache.h

[Go to the documentation of this file.](#)

```

00001
00005 /*
00006  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>
00007  *      economic rights: Technische Universität Dresden (Germany)
00008  *
00009  * License: see LICENSE.spdx (in this directory or the directories above)
00010  */
00011 #ifndef __L4SYS__INCLUDE__ARCH_X86__CACHE_H__
00012 #define __L4SYS__INCLUDE__ARCH_X86__CACHE_H__
00013
00014 L4_INLINE int
00015 l4_cache_clean_data(unsigned long start,
00016                    unsigned long end) L4_NOTHROW
00017 {
00018     (void)start; (void)end;
00019     return 0;
00020 }
00021
00022 L4_INLINE int
00023 l4_cache_flush_data(unsigned long start,
00024                    unsigned long end) L4_NOTHROW
00025 {
00026     (void)start; (void)end;
00027     return 0;
00028 }
00029
00030 L4_INLINE int
00031 l4_cache_inv_data(unsigned long start,
00032                  unsigned long end) L4_NOTHROW
00033 {
00034     (void)start; (void)end;
00035     return 0;
00036 }
00037
00038 L4_INLINE int
00039 l4_cache_coherent(unsigned long start,
00040                  unsigned long end) L4_NOTHROW
00041 {
00042     (void)start; (void)end;
00043     return 0;
00044 }
00045

```



## Namespaces

- namespace [L4](#)  
*L4 low-level kernel interface.*

## Macros

- #define [L4\\_DISABLE\\_COPY](#)(*\_class*)  
*Disable copy of a class.*

## Functions

- template<typename T, typename F>  
[Cap](#)< T > [L4::cap\\_dynamic\\_cast](#) ([Cap](#)< F > const &c) noexcept  
*dynamic\_cast for capabilities.*

## 16.449.1 Detailed Description

[L4::Cap](#) related definitions.

### Author

Alexander Warg [alexander.warg@os.inf.tu-dresden.de](mailto:alexander.warg@os.inf.tu-dresden.de)

Definition in file [capability](#).

## 16.449.2 Macro Definition Documentation

### 16.449.2.1 L4\_DISABLE\_COPY

```
#define L4_DISABLE_COPY(  
    _class)
```

#### Value:

```
public:  
    _class(_class const &) = delete; \br/>    _class operator = (_class const &) = delete; \br/>private:
```

Disable copy of a class.

### Parameters

<i>_class</i>	Name of the class that shall not have value copy semantics.
---------------	---

The typical use of this is:

```
class Non_value  
{  
    L4\_DISABLE\_COPY(Non_value)  
    ...  
}
```

Definition at line [52](#) of file [capability](#).

## 16.450 capability

[Go to the documentation of this file.](#)

```

00001 // vim:set ft=cpp: -*- Mode: C++ -*-
00009 /*
00010  * (c) 2008-2009,2015 Author(s)
00011  *     economic rights: Technische Universität Dresden (Germany)
00012  *
00013  * License: see LICENSE.spdx (in this directory or the directories above)
00014  */
00015 #pragma once
00016
00017 #include <l4/sys/consts.h>
00018 #include <l4/sys/types.h>
00019 #include <l4/sys/kobject>
00020 #include <l4/sys/task.h>
00021
00022 namespace L4
00023 {
00024
00025     /* Forward declarations for our kernel object classes. */
00026     class Task;
00027     class Thread;
00028     class Thread_group;
00029     class Factory;
00030     class Irq;
00031     class Log;
00032     class Vm;
00033     class Vcpu_context;
00034     class Kobject;
00035
00051     #if __cplusplus >= 201103L
00052     #   define L4_DISABLE_COPY(_class) \
00053         public: \
00054             _class(_class const &) = delete; \
00055             _class operator = (_class const &) = delete; \
00056         private:
00057     #else
00058     #   define L4_DISABLE_COPY(_class) \
00059         private: \
00060             _class(_class const &); \
00061             _class operator = (_class const &);
00062     #endif
00063
00064
00065     #define L4_KOBJECT_DISABLE_COPY(_class) \
00066         protected: \
00067             _class(); \
00068             L4_DISABLE_COPY(_class)
00069
00070
00071     #define L4_KOBJECT(_class) L4_KOBJECT_DISABLE_COPY(_class)
00072
00073     inline l4_msgtag_t
00074     Cap_base::validate(Cap<Task> task, l4_utcb_t *u) const noexcept
00075     {
00076         return is_valid() ? l4_task_cap_valid_u(task.cap(), _c, u)
00077             : l4_msgtag(0, 0, 0, 0);
00078     }
00079
00080     inline l4_msgtag_t
00081     Cap_base::validate(l4_utcb_t *u) const noexcept
00082     {
00083         return is_valid() ? l4_task_cap_valid_u(L4_BASE_TASK_CAP, _c, u)
00084             : l4_msgtag(0, 0, 0, 0);
00085     }
00086
00087 }; // namespace L4
00088
00089 #include <l4/sys/meta>
00090
00091 namespace L4 {
00092
00114     template< typename T, typename F >
00115     inline
00116     Cap<T> cap_dynamic_cast(Cap<F> const &c) noexcept
00117     {
00118         if (!c.is_valid())
00119             return Cap<T>::Invalid;
00120
00121         Cap<Meta> mc = cap_reinterpret_cast<Meta>(c);
00122         Type_info const *m = kobject_typeid<T>();
00123         if (m->proto() && l4_error(mc->supports(m->proto())) > 0)
00124             return Cap<T>(c.cap());
00125

```

```

00126 // FIXME: use generic checker
00127 #if 0
00128 if (l4_error(mc->supports(T::kobject_proto())) > 0)
00129     return Cap<T>(c.cap());
00130 #endif
00131
00132 return Cap<T>::Invalid;
00133 }
00134
00135 }


```

## 16.451 l4/sys/compiler.h File Reference

L4 compiler related defines.

```
#include <l4/sys/linkage.h>
```

Include dependency graph for compiler.h:



This graph shows which files directly or indirectly include this file:



### Macros

- **#define L4\_INLINE**  
*L4 Inline function attribute.*
- **#define L4\_ALWAYS\_INLINE**  
*Always inline a function.*
- **#define L4\_NOTHROW**  
*Mark a function declaration and definition as never throwing an exception.*
- **#define L4\_BEGIN\_DECLS**  
*Start section with C types and functions.*
- **#define L4\_END\_DECLS**  
*End section with C types and functions.*
- **#define L4\_CONSTEXPR**  
*Constexpr function attribute.*
- **#define L4\_NORETURN**

- *Noreturn function attribute.*
- **#define L4\_NOINSTRUMENT**  
*No instrumentation function attribute.*
- **#define L4\_HIDDEN**  
*Attribute to mark functions, variables, and data types as being explicitly hidden from users of a library.*
- **#define L4\_EXPORT**  
*Attribute to mark functions, variables, and data types as being exported from a library.*
- **#define L4\_LIKELY(x)**  
*Expression is likely to execute.*
- **#define L4\_UNLIKELY(x)**  
*Expression is unlikely to execute.*
- **#define L4\_STICKY(x)**  
*Mark symbol sticky (even not there).*
- **#define L4\_DEPRECATED(s)**  
*Mark symbol deprecated.*
- **#define L4\_stringify\_helper(x)**  
*stringify helper.*
- **#define L4\_stringify(x)**  
*stringify.*

## Functions

- unsigned long **l4\_align\_stack\_for\_direct\_fncall** (unsigned long stack)  
*Specify the desired alignment of the stack pointer.*
- void **l4\_barrier** (void)  
*Memory barrier.*
- void **l4\_mb** (void)  
*Memory barrier.*
- void **l4\_wmb** (void)  
*Write memory barrier.*
- **L4\_NORETURN** void **l4\_infinite\_loop** (void)  
*Infinite loop.*

## 16.451.1 Detailed Description

[L4](#) compiler related defines.

Definition in file [compiler.h](#).



## 16.452 compiler.h

[Go to the documentation of this file.](#)

```

00001 /*****
00002  */
00003  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00004  *      Alexander Warg <warg@os.inf.tu-dresden.de>,
00005  *      Frank Mehnert <fm3@os.inf.tu-dresden.de>,
00006  *      Jork Löser <jork@os.inf.tu-dresden.de>,
00007  *      Ronald Aigner <ra3@os.inf.tu-dresden.de>
00008  *      economic rights: Technische Universität Dresden (Germany)
00009  *
00010  * License: see LICENSE.spdx (in this directory or the directories above)
00011  */
00012 /*****
00013  */
00014 #ifndef __L4_COMPILER_H__
00015 #define __L4_COMPILER_H__
00016
00017 #if !defined(__ASSEMBLY__) && !defined(__ASSEMBLER__)
00018
00019 #ifndef L4_INLINE
00020 #ifndef __cplusplus
00021 #   ifdef __OPTIMIZE__
00022 #       define L4_INLINE_STATIC static __inline__
00023 #       define L4_INLINE_EXTERN extern __inline__
00024 #       ifdef __GNUC_STDC_INLINE__
00025 #           define L4_INLINE L4_INLINE_STATIC
00026 #       else
00027 #           define L4_INLINE L4_INLINE_EXTERN
00028 #       endif
00029 #   else /* ! __OPTIMIZE__ */
00030 #       define L4_INLINE static
00031 #   endif /* ! __OPTIMIZE__ */
00032 #else /* __cplusplus */
00033 #define L4_INLINE inline
00034 #endif /* __cplusplus */
00035 #elif defined DOXYGEN
00036 #define L4_INLINE inline
00037 #endif /* L4_INLINE */
00038 #define L4_ALWAYS_INLINE L4_INLINE __attribute__((__always_inline__))
00039
00040 #define L4_DECLARE_CONSTRUCTOR(func, prio) \
00041     static inline __attribute__((constructor(prio))) void func ## _ctor_func(void) { func(); }
00042
00043 #ifndef __cplusplus
00044 #define L4_NOTHROW_A __attribute__((nothrow))
00045 #define L4_NOTHROW
00046 #ifndef __BEGIN_DECLS
00047 #define __BEGIN_DECLS
00048 #endif
00049 #ifndef __END_DECLS
00050 #define __END_DECLS
00051 #endif
00052 #define L4_BEGIN_DECLS
00053 #define L4_END_DECLS
00054 #define L4_DEFAULT_PARAM(x)
00055 #else /* __cplusplus */
00056 #if __cplusplus >= 201103L
00057 #define L4_NOTHROW noexcept
00058 #else /* C++ < 11 */
00059 #define L4_NOTHROW throw()
00060 #endif
00061 #define L4_BEGIN_DECLS extern "C" {
00062 #define L4_END_DECLS }
00063 #if !defined __BEGIN_DECLS || defined DOXYGEN
00064 #define L4_BEGIN_DECLS extern "C" {
00065 #endif
00066 #if !defined __END_DECLS || defined DOXYGEN
00067 #define L4_END_DECLS }
00068 #endif
00069 #define L4_DEFAULT_PARAM(x) = x
00070 #endif /* __cplusplus */
00071
00072 /* Deprecation hints during compile -- remove later (2025+) */
00073 #ifndef EXTERN_C
00074 #define EXTERN_C DO_NOT_USE_EXTERN_C_ANY_MORE
00075 #endif
00076 #ifndef EXTERN_C_BEGIN

```

```

00181 #define EXTERN_C_BEGIN DO_NOT_USE_EXTERN_C_BEGIN_ANY_MORE__USE_L4_BEGIN_DECLS
00182 #endif
00183 #ifndef EXTERN_C_END
00184 #define EXTERN_C_END DO_NOT_USE_EXTERN_C_END_ANY_MORE__USE_L4_END_DECLS
00185 #endif
00186
00191 #if defined __cplusplus && __cplusplus >= 201402L
00192 # define L4_CONSTEXPR constexpr
00193 #else
00194 # define L4_CONSTEXPR
00195 #endif
00196
00201 #define L4_NORETURN __attribute__((noreturn))
00202
00203 #define L4_PURE __attribute__((pure))
00204
00209 #define L4_NOINSTRUMENT __attribute__((no_instrument_function))
00210 #ifndef L4_HIDDEN
00211 # define L4_HIDDEN __attribute__((visibility("hidden")))
00212 #endif
00213 #if !defined L4_EXPORT || defined DOXYGEN
00214 # define L4_EXPORT __attribute__((visibility("default")))
00215 #endif
00216 #ifndef L4_EXPORT_TYPE
00217 #   ifdef __cplusplus
00218 #       define L4_EXPORT_TYPE __attribute__((visibility("default")))
00219 #   else
00220 #       define L4_EXPORT_TYPE
00221 #   endif
00222 #endif
00223 #define L4_STRONG_ALIAS(name, aliasname) L4_STRONG_ALIAS(name, aliasname)
00224 #define L4_WEAK_ALIAS(name, aliasname) L4_WEAK_ALIAS(name, aliasname)
00225 #ifdef __clang__
00226 #define L4_STRONG_ALIAS(name, aliasname) \
00227     extern __typeof (name) aliasname __attribute__((alias (#name)));
00228 #define L4_WEAK_ALIAS(name, aliasname) \
00229     extern __typeof (name) aliasname __attribute__((weak, alias (#name)));
00230 #else
00231 #define L4_STRONG_ALIAS(name, aliasname) \
00232     extern __typeof (name) aliasname __attribute__((alias (#name), copy(name)));
00233 #define L4_WEAK_ALIAS(name, aliasname) \
00234     extern __typeof (name) aliasname __attribute__((weak, alias (#name), copy(name)));
00235 #endif
00236
00244 #if defined(__i386__) || defined(__amd64__) || \
00245     defined(__arm__) || defined(__aarch64__) || \
00246     defined(__mips__) || defined(__riscv__) || \
00247     defined(__powerpc__) || defined(__sparc__)
00248 # define L4_STACK_ALIGN __BIGGEST_ALIGNMENT__
00249 #else
00250 # error Define L4_STACK_ALIGN for this target!
00251 #endif
00252
00270 #if defined(__i386__) || defined(__amd64__)
00271 L4_INLINE unsigned long l4_align_stack_for_direct_fncall(unsigned long stack)
00272 {
00273     if ((stack & (L4_STACK_ALIGN - 1)) == (L4_STACK_ALIGN - sizeof(unsigned long)))
00274         return stack;
00275     return (stack & ~(L4_STACK_ALIGN)) - sizeof(unsigned long);
00276 }
00277 #else
00278 L4_INLINE unsigned long l4_align_stack_for_direct_fncall(unsigned long stack)
00279 {
00280     return stack & ~(L4_STACK_ALIGN);
00281 }
00282 #endif
00283
00284 #endif /* !__ASSEMBLY__ */
00285
00286 #include <l4/sys/linkage.h>
00287
00288 #define L4_LIKELY(x) __builtin_expect((x),1)
00289 #define L4_UNLIKELY(x) __builtin_expect((x),0)
00290
00291 /* Make sure that the function is not removed by optimization. Without the
00292  * "used" attribute, unreferenced static functions are removed. */
00293 #define L4_STICKY(x) __attribute__((used)) x
00294 #define L4_DEPRECATED(s) __attribute__((deprecated(s)))
00295
00296 #ifndef static_assert
00297 # if !defined(__cplusplus)
00298 #   define static_assert(x, y) _Static_assert(x, y)
00299 # elif __cplusplus < 201103L
00300 #   define static_assert(x, y) \
00301     extern int l4_static_assert[!(x)] __attribute__((unused))
00302 # endif
00303 #endif

```

```

00304
00305 #define L4_stringify_helper(x) #x
00306 #define L4_stringify(x)      L4_stringify_helper(x)
00307
00308 #ifdef __has_builtin
00309 #define L4_HAS_BUILTIN(def) __has_builtin(def)
00310 #else
00311 #define L4_HAS_BUILTIN(def) 0
00312 #endif
00313
00314 #ifndef __ASSEMBLER__
00318 L4_INLINE void l4_barrier(void);
00319
00323 L4_INLINE void l4_mb(void);
00324
00328 L4_INLINE void l4_wmb(void);
00329
00333 L4_INLINE L4_NORETURN void l4_infinite_loop(void);
00334
00335
00336 /* Implementations */
00337 L4_INLINE void l4_barrier(void)
00338 {
00339     __asm__ __volatile__ ("": : : "memory");
00340 }
00341
00342 L4_INLINE void l4_mb(void)
00343 {
00344     __asm__ __volatile__ ("": : : "memory");
00345 }
00346
00347 L4_INLINE void l4_wmb(void)
00348 {
00349     __asm__ __volatile__ ("": : : "memory");
00350 }
00351
00352 L4_INLINE L4_NORETURN void l4_infinite_loop(void)
00353 {
00354     while (1)
00355         l4_barrier();
00356 }
00357 #endif
00358
00360
00361 #endif /* !__L4_COMPILER_H__ */

```

## 16.453 amd64/l4/sys/arch/consts.h File Reference

Common [L4](#) constants, AMD64 version.

### Macros

- `#define L4_PAGESHIFT 12`  
*Size of a page, log2-based.*
- `#define L4_SUPERPAGESHIFT 21`  
*Size of a large page, log2-based.*

### 16.453.1 Detailed Description

Common [L4](#) constants, AMD64 version.

Definition in file [consts.h](#).

## 16.454 consts.h

[Go to the documentation of this file.](#)

```


00001 /*****
00007 */
00008 * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00009 *      Alexander Warg <warg@os.inf.tu-dresden.de>,
00010 *      Björn Döbel <doebel@os.inf.tu-dresden.de>,
00011 *      Torsten Frenzel <frenzel@os.inf.tu-dresden.de>
00012 *      economic rights: Technische Universität Dresden (Germany)
00013 *
00014 * License: see LICENSE.spdx (in this directory or the directories above)
00015 */
00016 /*****
00017 #ifndef __L4SYS__INCLUDE__ARCH_AMD64__CONSTS_H__
00018 #define __L4SYS__INCLUDE__ARCH_AMD64__CONSTS_H__
00019
00024 #define L4_PAGESHIFT      12
00025
00030 #define L4_SUPERPAGESHIFT 21
00031
00032 #endif /* ! __L4SYS__INCLUDE__ARCH_AMD64__CONSTS_H__ */

```

## 16.455 arm/l4/sys/arch/consts.h File Reference

Common [L4](#) constants, arm version.

#include <l4/sys/l4int.h>  
 Include dependency graph for consts.h:



### Macros

- #define [L4\\_PAGESHIFT](#) 12  
*Size of a page, log2-based.*
- #define [L4\\_SUPERPAGESHIFT](#) 21  
*Size of a large page, log2-based.*

### 16.455.1 Detailed Description

Common [L4](#) constants, arm version.

Definition in file [consts.h](#).

## 16.456 consts.h

[Go to the documentation of this file.](#)


```
00001
00006 /*
00007  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00008  *      Alexander Warg <warg@os.inf.tu-dresden.de>,
00009  *      Björn Döbel <doebel@os.inf.tu-dresden.de>
00010  *      economic rights: Technische Universität Dresden (Germany)
00011  *
00012  * License: see LICENSE.spdx (in this directory or the directories above)
00013  */
00014 #ifndef _L4_SYS_CONSTS_H
00015 #define _L4_SYS_CONSTS_H
00016
00017 /* L4 includes */
00018 #include <l4/sys/l4int.h>
00026 #define L4_PAGESHIFT 12
00027
00031 #define L4_SUPERPAGESHIFT 21
00032
00034
00035 #endif /* !_L4_SYS_CONSTS_H */
```

## 16.457 arm64/l4/sys/arch/consts.h File Reference

Common [L4](#) constants, arm version.

```
#include <l4/sys/l4int.h>
```

Include dependency graph for consts.h:



## Macros

- `#define L4_PAGESHIFT 12`  
*Size of a page, log2-based.*
- `#define L4_SUPERPAGESHIFT 21`  
*Size of a large page, log2-based.*

## 16.457.1 Detailed Description

Common [L4](#) constants, arm version.

Definition in file [consts.h](#).

## 16.458 consts.h

[Go to the documentation of this file.](#)


```
00001
00006 /*
00007  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00008  *      Alexander Warg <warg@os.inf.tu-dresden.de>,
00009  *      Björn Döbel <doebel@os.inf.tu-dresden.de>
00010  *      economic rights: Technische Universität Dresden (Germany)
00011  *
00012  * License: see LICENSE.spdx (in this directory or the directories above)
00013  */
00014 #ifndef _L4_SYS_CONSTS_H
00015 #define _L4_SYS_CONSTS_H
00016
00017 /* L4 includes */
00018 #include <l4/sys/l4int.h>
00026 #define L4_PAGESHIFT    12
00027
00031 #define L4_SUPERPAGESHIFT 21
00032
00034
00035 #endif /* !_L4_SYS_CONSTS_H */
```

## 16.459 l4/re/consts.h File Reference


Constants.

```
#include <l4/sys/consts.h>
```

Include dependency graph for consts.h:



This graph shows which files directly or indirectly include this file:



## Enumerations

- `enum`  
*Defaults for local thread priorities.*

### 16.459.1 Detailed Description

Constants.

Definition in file [consts.h](#).

## 16.459.2 Enumeration Type Documentation

### 16.459.2.1 anonymous enum

anonymous enum

Defaults for local thread priorities.

Priorities are to be seen as local. These are used by the loader and libpthread. They are to be understood as 'local', which means the actual priority of the thread (as seen by the kernel) is the base priority as defined by the scheduler plus the local priority.

Definition at line 28 of file [consts.h](#).

## 16.460 consts.h

[Go to the documentation of this file.](#)

```

00001
00005 /*
00006  * (c) 2008-2009 Alexander Warg <warg@os.inf.tu-dresden.de>
00007  *     economic rights: Technische Universität Dresden (Germany)
00008  *
00009  * License: see LICENSE.spdx (in this directory or the directories above)
00010  */
00011 #pragma once
00012
00013 #include <l4/sys/consts.h>
00014
00015 enum
00016 {
00017     L4RE_THIS_TASK_CAP = 1UL « L4_CAP_SHIFT,
00018 };
00019
00020 enum
00021 {
00030     L4RE_MAIN_THREAD_PRIO = 2, /* Priority of the main thread */
00031 };
00032

```

## 16.461 l4/sys/consts.h File Reference


Common constants.

```
#include <l4/sys/arch/consts.h>
```

```
#include <l4/sys/compiler.h>
```

```
#include <l4/sys/l4int.h>
```

Include dependency graph for consts.h:





This graph shows which files directly or indirectly include this file:



## Macros

- `#define L4_SYSF_NONE`  
*Capability selector flags.*
- `#define L4_SYSF_SEND`  
*Send-phase flag.*
- `#define L4_SYSF_RECV`  
*Receive-phase flag.*
- `#define L4_SYSF_OPEN_WAIT`  
*Open-wait flag.*
- `#define L4_SYSF_REPLY`  
*Reply flag.*
- `#define L4_SYSF_CALL`  
*Call flags (combines send and receive).*
- `#define L4_SYSF_WAIT`  
*Wait flags (combines receive and open wait).*
- `#define L4_SYSF_SEND_AND_WAIT`  
*Send-and-wait flags.*
- `#define L4_SYSF_REPLY_AND_WAIT`  
*Reply-and-wait flags.*
- `#define L4_CAP_SHIFT`  
*Capability index shift.*
- `#define L4_CAP_SIZE (1UL << L4_CAP_SHIFT)`
- `#define L4_CAP_OFFSET`  
*Offset of two consecutive capability selectors.*
- `#define L4_CAP_MASK`  
*Mask to get only the relevant bits of an `l4_cap_idx_t`.*
- `#define L4_INVALID_CAP`  
*Invalid capability selector.*
- `#define L4_PAGESIZE`  
*Minimal page size (in bytes).*
- `#define L4_PAGEMASK`  
*Mask for the page number.*
- `#define L4_LOG2_PAGESIZE`  
*Number of bits used for page offset.*
- `#define L4_SUPERPAGESIZE`  
*Size of a large page.*
- `#define L4_SUPERPAGEMASK`  
*Mask for the number of a large page.*
- `#define L4_LOG2_SUPERPAGESIZE`  
*Number of bits used as offset for a large page.*
- `#define L4_INVALID_PTR ((void *)L4_INVALID_ADDR)`  
*Invalid address as pointer type.*

## Enumerations

- enum [l4\\_unmap\\_flags\\_t](#) { [L4\\_FP\\_ALL\\_SPACES](#) , [L4\\_FP\\_DELETE\\_OBJ](#) , [L4\\_FP\\_OTHER\\_SPACES](#) }  
*Flags for the unmap operation.*
- enum [l4\\_msg\\_item\\_consts\\_t](#) {  
[L4\\_ITEM\\_MAP](#) = 8 , [L4\\_ITEM\\_CONT](#) = 1 , [L4\\_MAP\\_ITEM\\_GRANT](#) = 2 , [L4\\_MAP\\_ITEM\\_MAP](#) = 0 ,  
[L4\\_RCV\\_ITEM\\_FORWARD\\_MAPPINGS](#) = 1 , [L4\\_RCV\\_ITEM\\_SINGLE\\_CAP](#) = [L4\\_ITEM\\_MAP](#) | 2 ,  
[L4\\_RCV\\_ITEM\\_LOCAL\\_ID](#) = 4 }  
*Constants for message items.*
- enum [l4\\_buffer\\_desc\\_consts\\_t](#) { [L4\\_BDR\\_MEM\\_SHIFT](#) = 0 , [L4\\_BDR\\_IO\\_SHIFT](#) = 5 , [L4\\_BDR\\_OBJ\\_SHIFT](#) = 10 , [L4\\_BDR\\_OFFSET\\_MASK](#) = (1UL << 20) - 1 }  
*Constants for buffer descriptors.*
- enum [l4\\_default\\_caps\\_t](#) {  
[L4\\_BASE\\_TASK\\_CAP](#) , [L4\\_BASE\\_FACTORY\\_CAP](#) , [L4\\_BASE\\_THREAD\\_CAP](#) , [L4\\_BASE\\_PAGER\\_CAP](#) ,  
[L4\\_BASE\\_LOG\\_CAP](#) , [L4\\_BASE\\_ICU\\_CAP](#) , [L4\\_BASE\\_SCHEDULER\\_CAP](#) , [L4\\_BASE\\_IOMMU\\_CAP](#) ,  
[L4\\_BASE\\_DEBUGGER\\_CAP](#) , [L4\\_BASE\\_ARM\\_SMCCC\\_CAP](#) , [L4\\_BASE\\_CAPS\\_LAST\\_P1](#) , [L4\\_BASE\\_CAPS\\_LAST](#)  
= [L4\\_BASE\\_CAPS\\_LAST\\_P1](#) - 1 }  
*Default capabilities setup for the initial tasks.*
- enum [l4\\_addr\\_consts\\_t](#) { [L4\\_INVALID\\_ADDR](#) = ~0UL }  
*Address related constants.*

## Functions

- [l4\\_addr\\_t l4\\_trunc\\_page](#) ([l4\\_addr\\_t](#) address) [L4\\_NOTHROW](#)  
*Round an address down to the next lower page boundary.*
- [l4\\_addr\\_t l4\\_trunc\\_size](#) ([l4\\_addr\\_t](#) address, unsigned char bits) [L4\\_NOTHROW](#)  
*Round an address down to the next lower flexpage with size bits.*
- [l4\\_addr\\_t l4\\_round\\_page](#) ([l4\\_addr\\_t](#) address) [L4\\_NOTHROW](#)  
*Round address up to the next page.*
- [l4\\_addr\\_t l4\\_round\\_size](#) ([l4\\_addr\\_t](#) value, unsigned char bits) [L4\\_NOTHROW](#)  
*Round value up to the next alignment with bits size.*
- unsigned [l4\\_bytes\\_to\\_mwords](#) (unsigned size) [L4\\_NOTHROW](#)  
*Determine how many machine words ([l4\\_umword\\_t](#)) are required to store a buffer of 'size' bytes.*

### 16.461.1 Detailed Description

Common constants.

Definition in file [consts.h](#).

### 16.461.2 Macro Definition Documentation

#### 16.461.2.1 L4\_CAP\_SIZE

```
#define L4_CAP_SIZE (1UL << L4\_CAP\_SHIFT)
```

**Deprecated** Superseded by [L4\\_CAP\\_OFFSET](#).

Definition at line 139 of file [consts.h](#).

### 16.461.2.2 L4\_SYSF\_CALL

```
#define L4_SYSF_CALL
```

Call flags (combines send and receive).

Combines [L4\\_SYSF\\_SEND](#) and [L4\\_SYSF\\_RECV](#).

Definition at line 107 of file [consts.h](#).

Referenced by [l4\\_ipc\\_call\(\)](#).

### 16.461.2.3 L4\_SYSF\_OPEN\_WAIT

```
#define L4_SYSF_OPEN_WAIT
```

Open-wait flag.

This flag indicates that the receive operation (see [L4\\_SYSF\\_RECV](#)) shall be an *open wait*. *Open wait* means that the invoking thread shall wait for a message from any possible sender and *not* from the sender denoted by the capability.

Definition at line 90 of file [consts.h](#).

### 16.461.2.4 L4\_SYSF\_RECV

```
#define L4_SYSF_RECV
```

Receive-phase flag.

Setting this flag in a capability selector induces a receive phase, this means the invoking thread waits for a message from the object denoted by the capability. For a send phase see [L4\\_SYSF\\_SEND](#).

Definition at line 79 of file [consts.h](#).

Referenced by [l4\\_ipc\\_receive\(\)](#).

### 16.461.2.5 L4\_SYSF\_REPLY

```
#define L4_SYSF_REPLY
```

Reply flag.

This flag indicates that the send phase shall use the in-kernel reply capability instead of the capability denoted by the selector index.

Definition at line 99 of file [consts.h](#).

Referenced by [L4::Server< LOOP\\_HOOKS >::reply\\_n\\_wait\(\)](#).

### 16.461.2.6 L4\_SYSF\_REPLY\_AND\_WAIT

```
#define L4_SYSF_REPLY_AND_WAIT
```

Reply-and-wait flags.

Combines [L4\\_SYSF\\_SEND](#), [L4\\_SYSF\\_REPLY](#), and [L4\\_SYSF\\_WAIT](#).

Definition at line 131 of file [consts.h](#).

Referenced by [l4\\_ipc\\_reply\\_and\\_wait\(\)](#).

### 16.461.2.7 L4\_SYSF\_SEND

```
#define L4_SYSF_SEND
```

Send-phase flag.

Setting this flag in a capability selector induces a send phase, this means a message is sent to the object denoted by the capability. For receive phase see [L4\\_SYSF\\_RECV](#).

In [l4\\_vcpu\\_state\\_t::user\\_task](#) this flag means that the kernel has cached the user task capability internally, see [l4\\_thread\\_vcpu\\_resume\\_commit\(\)](#).

Definition at line 68 of file [consts.h](#).

Referenced by [l4\\_ipc\\_send\(\)](#).

### 16.461.2.8 L4\_SYSF\_SEND\_AND\_WAIT

```
#define L4_SYSF_SEND_AND_WAIT
```

Send-and-wait flags.

Combines [L4\\_SYSF\\_SEND](#) and [L4\\_SYSF\\_WAIT](#).

Definition at line 123 of file [consts.h](#).

Referenced by [l4\\_ipc\\_send\\_and\\_wait\(\)](#).

### 16.461.2.9 L4\_SYSF\_WAIT

```
#define L4_SYSF_WAIT
```

Wait flags (combines receive and open wait).

Combines [L4\\_SYSF\\_RECV](#) and [L4\\_SYSF\\_OPEN\\_WAIT](#).

Definition at line 115 of file [consts.h](#).

Referenced by [l4\\_ipc\\_wait\(\)](#).

## 16.462 consts.h

[Go to the documentation of this file.](#)

```

00001
00006 /*
00007  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00008  *      Alexander Warg <warg@os.inf.tu-dresden.de>,
00009  *      Björn Döbel <doebel@os.inf.tu-dresden.de>,
00010  *      Torsten Frenzel <frenzel@os.inf.tu-dresden.de>
00011  *      economic rights: Technische Universität Dresden (Germany)
00012  *
00013  * License: see LICENSE.spdx (in this directory or the directories above)
00014  */
00015 #ifndef __L4_SYS__INCLUDE__CONSTS_H__
00016 #define __L4_SYS__INCLUDE__CONSTS_H__
00017
00018 #include <l4/sys/arch/consts.h>
00019 #include <l4/sys/compiler.h>
00020 #include <l4/sys/l4int.h>
00021
00055 #define L4_SYSF_NONE      0x00
00056
00068 #define L4_SYSF_SEND      0x01
00069
00079 #define L4_SYSF_RECV      0x02
00080
00090 #define L4_SYSF_OPEN_WAIT 0x04
00091
00099 #define L4_SYSF_REPLY     0x08
00100
00107 #define L4_SYSF_CALL      (L4_SYSF_SEND | L4_SYSF_RECV)
00108
00115 #define L4_SYSF_WAIT      (L4_SYSF_OPEN_WAIT | L4_SYSF_RECV)
00116
00123 #define L4_SYSF_SEND_AND_WAIT (L4_SYSF_OPEN_WAIT | L4_SYSF_CALL)
00124
00131 #define L4_SYSF_REPLY_AND_WAIT (L4_SYSF_WAIT | L4_SYSF_SEND | L4_SYSF_REPLY)
00132
00137 #define L4_CAP_SHIFT      12UL
00139 #define L4_CAP_SIZE        (1UL < L4_CAP_SHIFT)
00144 #define L4_CAP_OFFSET      (1UL < L4_CAP_SHIFT)
00150 #define L4_CAP_MASK        (~0UL < (L4_CAP_SHIFT - 1))
00152 #define L4_INVALID_CAP      (~0UL < (L4_CAP_SHIFT - 1))
00153
00154 #define L4_INVALID_CAP_BIT (1UL < (L4_CAP_SHIFT - 1))
00155
00156 enum l4_sched_consts_t
00157 {
00158     L4_SCHED_MIN_PRIO = 1,
00159     L4_SCHED_MAX_PRIO = 255,
00160 };
00161
00167 enum l4_unmap_flags_t
00168 {
00181     L4_FP_ALL_SPACES    = 0x80000000UL,
00182
00195     L4_FP_DELETE_OBJ    = 0xc0000000UL,
00196
00203     L4_FP_OTHER_SPACES  = 0x00UL
00204 };
00205
00210 enum l4_msg_item_consts_t
00211 {
00212     L4_ITEM_MAP          = 8,
00213
00218     L4_ITEM_CONT         = 1,
00219
00220     // send
00243     L4_MAP_ITEM_GRANT    = 2,
00244
00245     L4_MAP_ITEM_MAP      = 0,
00246
00247     // receive
00258     L4_RCV_ITEM_FORWARD_MAPPINGS = 1,
00259
00273     L4_RCV_ITEM_SINGLE_CAP = L4_ITEM_MAP | 2,
00274
00294     L4_RCV_ITEM_LOCAL_ID   = 4,
00295 };
00296
00301 enum l4_buffer_desc_consts_t
00302 {
00303     L4_BDR_MEM_SHIFT     = 0,
00304     L4_BDR_IO_SHIFT      = 5,
00305     L4_BDR_OBJ_SHIFT     = 10,

```

```

00306     L4_BDR_OFFSET_MASK = (1UL << 20) - 1,
00307 };
00308
00322 enum l4_default_caps_t
00323 {
00325     L4_BASE_TASK_CAP      = 1UL << L4_CAP_SHIFT,
00327     L4_BASE_FACTORY_CAP   = 2UL << L4_CAP_SHIFT,
00329     L4_BASE_THREAD_CAP    = 3UL << L4_CAP_SHIFT,
00337     L4_BASE_PAGER_CAP     = 4UL << L4_CAP_SHIFT,
00345     L4_BASE_LOG_CAP       = 5UL << L4_CAP_SHIFT,
00347     L4_BASE_ICU_CAP       = 6UL << L4_CAP_SHIFT,
00349     L4_BASE_SCHEDULER_CAP = 7UL << L4_CAP_SHIFT,
00356     L4_BASE_IOMMU_CAP     = 8UL << L4_CAP_SHIFT,
00364     L4_BASE_DEBUGGER_CAP  = 10UL << L4_CAP_SHIFT,
00371     L4_BASE_ARM_SMCCC_CAP = 11UL << L4_CAP_SHIFT,
00372
00374     L4_BASE_CAPS_LAST_P1,
00376     L4_BASE_CAPS_LAST = L4_BASE_CAPS_LAST_P1 - 1
00377 };
00378
00389 #define L4_PAGESIZE      (1UL << L4_PAGESHIFT)
00390
00398 #define L4_PAGEMASK     (~(L4_PAGESIZE - 1))
00399
00407 #define L4_LOG2_PAGESIZE L4_PAGESHIFT
00408
00416 #define L4_SUPERPAGESIZE (1UL << L4_SUPERPAGESHIFT)
00417
00425 #define L4_SUPERPAGEMASK (~(L4_SUPERPAGESIZE - 1))
00426
00433 #define L4_LOG2_SUPERPAGESIZE L4_SUPERPAGESHIFT
00434
00445 L4_INLINE l4_addr_t l4_trunc_page(l4_addr_t address) L4_NOTHROW;
00446 L4_INLINE l4_addr_t l4_trunc_page(l4_addr_t address) L4_NOTHROW
00447 { return address & L4_PAGEMASK; }
00448
00456 L4_INLINE l4_addr_t l4_trunc_size(l4_addr_t address, unsigned char bits) L4_NOTHROW;
00457 L4_INLINE l4_addr_t l4_trunc_size(l4_addr_t address, unsigned char bits) L4_NOTHROW
00458 { return address & (~0UL << bits); }
00459
00470 L4_INLINE l4_addr_t l4_round_page(l4_addr_t address) L4_NOTHROW;
00471 L4_INLINE l4_addr_t l4_round_page(l4_addr_t address) L4_NOTHROW
00472 { return (address + L4_PAGESIZE - 1) & L4_PAGEMASK; }
00473
00481 L4_INLINE l4_addr_t l4_round_size(l4_addr_t value, unsigned char bits) L4_NOTHROW;
00482 L4_INLINE l4_addr_t l4_round_size(l4_addr_t value, unsigned char bits) L4_NOTHROW
00483 { return (value + (1UL << bits) - 1) & (~0UL << bits); }
00484
00493 L4_INLINE unsigned l4_bytes_to_mwords(unsigned size) L4_NOTHROW;
00494 L4_INLINE unsigned l4_bytes_to_mwords(unsigned size) L4_NOTHROW
00495 { return (size + sizeof(l4_umword_t) - 1) / sizeof(l4_umword_t); }
00496
00501 enum l4_addr_consts_t {
00503     L4_INVALID_ADDR = ~0UL
00504 };
00505
00510 #define L4_INVALID_PTR ((void *)L4_INVALID_ADDR)
00511
00512 #ifndef NULL
00513 #ifndef __cplusplus
00514 # define NULL ((void *)0)
00518 #elif __cplusplus >= 201103L
00519 # define NULL nullptr
00520 #else
00521 # define NULL 0
00522 #endif
00523 #endif
00524
00525 #endif /* ! __L4_SYS__INCLUDE__CONSTS_H__ */

```

## 16.463 x86/i4/sys/arch/consts.h File Reference

Common [L4](#) constants, x86 version.

### Macros

- `#define L4_PAGESHIFT 12`

*Size of a page log2-based.*

- `#define L4_SUPERPAGESHIFT 22`

*Size of a large page log2-based.*

## 16.463.1 Detailed Description

Common [L4](#) constants, x86 version.

Definition in file [consts.h](#).

## 16.464 consts.h

[Go to the documentation of this file.](#)

```
00001 /*****
00007 */
00008 * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00009 *      Alexander Warg <warg@os.inf.tu-dresden.de>,
00010 *      Björn Döbel <doebel@os.inf.tu-dresden.de>,
00011 *      Lars Reuther <reuther@os.inf.tu-dresden.de>
00012 *      economic rights: Technische Universität Dresden (Germany)
00013 *
00014 * License: see LICENSE.spdx (in this directory or the directories above)
00015 */
00016 /*****
00017 #ifndef __L4SYS__INCLUDE__ARCH_X86__CONSTS_H__
00018 #define __L4SYS__INCLUDE__ARCH_X86__CONSTS_H__
00019
00024 #define L4_PAGESHIFT      12
00025
00030 #define L4_SUPERPAGESHIFT 22
00031
00032 #endif /* ! __L4SYS__INCLUDE__ARCH_X86__CONSTS_H__ */
```

## 16.465 capability.h

```
00001
00002 #pragma once
00003
00004 #include <l4/sys/consts.h>
00005 #include <l4/sys/types.h>
00006 #include <l4/sys/task.h>
00007
00008 namespace L4 {
00009
00010 class Task;
00011 class Kobject;
00012
00013 template< typename T > class L4_EXPORT Cap;
00014
00025 class L4_EXPORT Cap_base
00026 {
00027 public:
00029     enum No_init_type
00030     {
00034         No_init
00035     };
00036
00040     enum Cap_type
00041     {
00042         Invalid = L4_INVALID_CAP
00043     };
00044
00049     l4_cap_idx_t cap() const noexcept { return _c; }
00050
00057     bool is_valid() const noexcept { return !(_c & L4_INVALID_CAP_BIT); }
00058
00062     int invalid_cap_error() const noexcept { return _c & ~L4_INVALID_CAP_BIT; }
00063
00064     explicit operator bool () const noexcept
```

```

00065 { return !(_c & L4_INVALID_CAP_BIT); }
00066
00074 l4_fpage_t fpage(unsigned rights = L4_CAP_FPAGE_RWS) const noexcept
00075 { return l4_obj_fpage(_c, 0, rights); }
00076
00086 l4_umword_t snd_base(unsigned grant = L4_MAP_ITEM_MAP,
00087                      l4_cap_idx_t base = L4_INVALID_CAP) const noexcept
00088 {
00089     if (base == L4_INVALID_CAP)
00090         base = _c;
00091     return l4_map_obj_control(base, grant);
00092 }
00093
00094
00098 bool operator == (Cap_base const &o) const noexcept
00099 { return _c == o._c; }
00100
00104 bool operator != (Cap_base const &o) const noexcept
00105 { return _c != o._c; }
00106
00120 inline l4_msgtag_t validate(l4_utcb_t *u = l4_utcb()) const noexcept;
00121
00136 inline l4_msgtag_t validate(Cap<Task> task,
00137                             l4_utcb_t *u = l4_utcb()) const noexcept;
00138
00142 void invalidate() noexcept { _c = L4_INVALID_CAP; }
00143 protected:
00149 explicit Cap_base(l4_cap_idx_t c) noexcept : _c(c) {}
00153 explicit Cap_base(Cap_type cap) noexcept : _c(cap) {}
00154
00160 explicit Cap_base(l4_default_caps_t cap) noexcept : _c(cap) {}
00161
00165 explicit Cap_base() noexcept {}
00166
00176 void move(Cap_base const &src) const
00177 {
00178     if (!is_valid() || !src.is_valid())
00179         return;
00180
00181     l4_task_map(L4_BASE_TASK_CAP, L4_BASE_TASK_CAP, src.fpage(L4_CAP_FPAGE_RWSD),
00182                snd_base(L4_MAP_ITEM_GRANT) | L4_FPAGE_C_OBJ_RIGHTS);
00183 }
00184
00192 void copy(Cap_base const &src) const
00193 {
00194     if (!is_valid() || !src.is_valid())
00195         return;
00196
00197     l4_task_map(L4_BASE_TASK_CAP, L4_BASE_TASK_CAP, src.fpage(L4_CAP_FPAGE_RWSD),
00198                snd_base() | L4_FPAGE_C_OBJ_RIGHTS);
00199 }
00200
00203 l4_cap_idx_t _c;
00204 };
00205
00206
00222 template< typename T >
00223 class L4_EXPORT Cap : public Cap_base
00224 {
00225 private:
00226     friend class L4::Kobject;
00227
00239     explicit Cap(T const *p) noexcept
00240     : Cap_base(reinterpret_cast<l4_cap_idx_t>(p)) {}
00241
00242 public:
00243
00250     template< typename From >
00251     static void check_convertible_from() noexcept
00252     {
00253         using To = T;
00254         [[maybe_unused]] To* t = static_cast<From*>(nullptr);
00255     }
00256
00263     template< typename From >
00264     static void check_castable_from() noexcept
00265     {
00266         using To = T;
00267         [[maybe_unused]] To *t = static_cast<To *>(static_cast<From *>(nullptr));
00268     }
00269
00274     template< typename O >
00275     Cap(Cap<O> const &o) noexcept : Cap_base(o.cap())
00276     { check_convertible_from<O>(); }
00277
00282     Cap(Cap_type cap) noexcept : Cap_base(cap) {}
00283

```



```

00288     Cap(l4_default_caps_t cap) noexcept : Cap_base(cap) {}
00289
00294     explicit Cap(l4_cap_idx_t idx = L4_INVALID_CAP) noexcept : Cap_base(idx) {}
00295
00299     explicit Cap(No_init_type) noexcept {}
00300
00307     Cap move(Cap const &src) const
00308     {
00309         Cap_base::move(src);
00310         return *this;
00311     }
00312
00317     Cap copy(Cap const &src) const
00318     {
00319         Cap_base::copy(src);
00320         return *this;
00321     }
00322
00326     T *operator -> () const noexcept { return reinterpret_cast<T*>(_c); }
00327 };
00328
00329
00340 template<>
00341 class L4_EXPORT Cap<void> : public Cap_base
00342 {
00343 public:
00344
00345     explicit Cap(void const *p) noexcept
00346     : Cap_base(reinterpret_cast<l4_cap_idx_t>(p)) {}
00347
00351     Cap(Cap_type cap) noexcept : Cap_base(cap) {}
00352
00357     Cap(l4_default_caps_t cap) noexcept : Cap_base(cap) {}
00358
00363     explicit Cap(l4_cap_idx_t idx = L4_INVALID_CAP) noexcept : Cap_base(idx) {}
00364     explicit Cap(No_init_type) noexcept {}
00365
00366     template< typename From >
00367     static void check_convertible_from() noexcept {}
00368
00369     template< typename From >
00370     static void check_castable_from() noexcept {}
00371
00378     Cap move(Cap const &src) const
00379     {
00380         Cap_base::move(src);
00381         return *this;
00382     }
00383
00388     Cap copy(Cap const &src) const
00389     {
00390         Cap_base::copy(src);
00391         return *this;
00392     }
00393
00394     template< typename T >
00395     Cap(Cap<T> const &o) noexcept : Cap_base(o.cap()) {}
00396 };
00397
00414 template< typename T, typename F >
00415 inline
00416 Cap<T> cap_cast(Cap<F> const &c) noexcept
00417 {
00418     Cap<T>::template check_castable_from<F>();
00419     return Cap<T>(c.cap());
00420 }
00421
00422 // gracefully deal with L4::Kobject ambiguity
00423 template< typename T >
00424 inline
00425 Cap<T> cap_cast(Cap<L4::Kobject> const &c) noexcept
00426 {
00427     return Cap<T>(c.cap());
00428 }
00429
00445 template< typename T, typename F >
00446 inline
00447 Cap<T> cap_reinterpret_cast(Cap<F> const &c) noexcept
00448 {
00449     return Cap<T>(c.cap());
00450 }
00451
00452 }

```



## 16.467 consts

[Go to the documentation of this file.](#)

```

00001 // -*- Mode: C++ -*-
00002 // vim:ft=cpp
00003 /*
00004  * (c) 2008-2009 Alexander Warg <warg@os.inf.tu-dresden.de>
00005  *      economic rights: Technische Universität Dresden (Germany)
00006  *
00007  * License: see LICENSE.spdx (in this directory or the directories above)
00008  */
00009 #pragma once
00010 #include <l4/sys/capability>
00011 #include <l4/sys/consts.h>
00012 #include <l4/re/env.h>
00013 namespace L4Re {
00014     static L4::Cap<L4::Task>::Cap_type const This_task
00015         = static_cast<L4::Cap<L4::Task>::Cap_type>(L4RE_THIS_TASK_CAP);
00016 }

```

## 16.468 consts

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00002 #pragma once
00003 #include <l4/sys/consts.h>
00004 namespace L4 {
00005     template<typename T>
00006     constexpr T trunc_order(T val, unsigned char order)
00007     {
00008         return val & ((~T(0)) << order);
00009     }
00010     template<typename T>
00011     constexpr T round_order(T val, unsigned char order)
00012     {
00013         return (val + (T(1) << order) - T(1)) & ((~T(0)) << order);
00014     }
00015     template<typename T>
00016     constexpr T trunc_page(T val)
00017     {
00018         return trunc_order(val, L4_PAGESHIFT);
00019     }
00020     template<typename T>
00021     constexpr T round_page(T val)
00022     {
00023         return round_order(val, L4_PAGESHIFT);
00024     }
00025     template<typename T>
00026     inline unsigned char
00027     max_order(unsigned char order, T addr,
00028               T min_addr, T max_addr,
00029               T hotspot = T(0))
00030     {
00031         while (order < 30 /* limit to 1GB flexpages */)
00032         {
00033             T mask;
00034             T base = trunc_order(addr, order + 1);
00035             if (base < min_addr)
00036                 return order;
00037             if (base + (T(1) << (order + 1)) - T(1) > max_addr - T(1))
00038                 return order;
00039             mask = ~(~T(0) << (order + 1));
00040             if (hotspot == ~T(0) || ((addr ^ hotspot) & mask))
00041                 break;
00042             ++order;
00043         }
00044         return order;
00045     }

```

```

00073     }
00074
00075 }

```

## 16.469 ipc\_array

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00002 /*
00003  * (c) 2014 Alexander Warg <alexander.warg@kernkonzept.com>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007 #pragma once
00008
00009 #include "types"
00010 #include "ipc_basics"
00011 #include "ipc_types"
00012
00013 namespace L4 { namespace Ipc L4_EXPORT {
00014
00015     typedef unsigned short Array_len_default;
00016
00017     template< typename ELEM_TYPE, typename LEN_TYPE = Array_len_default >
00018     struct Array_ref
00019     {
00020         typedef ELEM_TYPE *ptr_type;
00021         typedef LEN_TYPE len_type;
00022
00023         len_type length;
00024         ptr_type data;
00025         Array_ref() = default;
00026         Array_ref(len_type length, ptr_type data)
00027             : length(length), data(data)
00028         {}
00029
00030         template<typename X> struct Non_const
00031         { typedef Array_ref<X, LEN_TYPE> type; };
00032
00033         template<typename X> struct Non_const<X const>
00034         { typedef Array_ref<X, LEN_TYPE> type; };
00035
00036         Array_ref(typename Non_const<ELEM_TYPE>::type const &other)
00037             : length(other.length), data(other.data)
00038         {}
00039
00040         Array_ref &operator = (typename Non_const<ELEM_TYPE>::type const &other)
00041         {
00042             this->length = other.length;
00043             this->data = other.data;
00044             return *this;
00045         }
00046     };
00047
00048     template<typename ELEM_TYPE, typename LEN_TYPE = Array_len_default>
00049     struct Array : Array_ref<ELEM_TYPE, LEN_TYPE>
00050     {
00051         Array() {}
00052         Array(LEN_TYPE length, ELEM_TYPE *data)
00053             : Array_ref<ELEM_TYPE, LEN_TYPE>(length, data)
00054         {}
00055
00056         template<typename X> struct Non_const
00057         { typedef Array<X, LEN_TYPE> type; };
00058
00059         template<typename X> struct Non_const<X const>
00060         { typedef Array<X, LEN_TYPE> type; };
00061
00062         Array(typename Non_const<ELEM_TYPE>::type const &other)
00063             : Array_ref<ELEM_TYPE, LEN_TYPE>(other.length, other.data)
00064         {}
00065
00066         Array &operator = (typename Non_const<ELEM_TYPE>::type const &other)
00067         {
00068             this->length = other.length;
00069             this->data = other.data;
00070             return *this;
00071         }
00072     };
00073
00074     template< typename ELEM_TYPE,
00075              typename LEN_TYPE = Array_len_default,
00076              LEN_TYPE MAX      = (L4_UTCB_GENERIC_DATA_SIZE *
00077                                   sizeof(l4_umword_t)) / sizeof(ELEM_TYPE) >

```

```

00126 struct Array_in_buf
00127 {
00128     typedef Array_ref<ELEM_TYPE, LEN_TYPE> array;
00129     typedef Array_ref<ELEM_TYPE const, LEN_TYPE> const_array;
00130
00132     ELEM_TYPE data[MAX];
00134     LEN_TYPE length;
00135
00137     void copy_in(const_array a)
00138     {
00139         length = a.length;
00140         if (length > MAX)
00141             length = MAX;
00142
00143         for (LEN_TYPE i = 0; i < length; ++i)
00144             data[i] = a.data[i];
00145     }
00146
00148     Array_in_buf(const_array a) { copy_in(a); }
00150     Array_in_buf(array a) { copy_in(a); }
00151 };
00152
00153 // implementation details for transmission
00154 namespace Msg {
00155
00157 template<typename A, typename LEN>
00158 struct Elem< Array<A, LEN> >
00159 {
00161     typedef Array<A, LEN> arg_type;
00163     typedef Array_ref<A, LEN> svr_type;
00164     typedef svr_type svr_arg_type;
00165     enum { Is_optional = false };
00166 };
00167
00169 template<typename A, typename LEN>
00170 struct Elem< Array<A, LEN> & >
00171 {
00173     typedef Array<A, LEN> &arg_type;
00175     typedef Array_ref<A, LEN> svr_type;
00177     typedef svr_type &svr_arg_type;
00178     enum { Is_optional = false };
00179 };
00180
00182 template<typename A, typename LEN>
00183 struct Elem< Array_ref<A, LEN> & >
00184 {
00186     typedef Array_ref<A, LEN> &arg_type;
00188     typedef Array_ref<typename L4::Types::Remove_const<A>::type, LEN> svr_type;
00190     typedef svr_type &svr_arg_type;
00191     enum { Is_optional = false };
00192 };
00193
00194 template<typename A> struct Class<Array<A> > : Class<A>::type {};
00195 template<typename A> struct Class<Array_ref<A> > : Class<A>::type {};
00196
00197 namespace Detail {
00198
00199 template<typename A, typename LEN, typename ARRAY, bool REF>
00200 struct Clnt_val_ops_d_in : Clnt_noops<ARRAY>
00201 {
00202     using Clnt_noops<ARRAY>::to_msg;
00203     static int to_msg(char *msg, unsigned offset, unsigned limit,
00204                      ARRAY a, Dir_in, Cls_data)
00205     {
00206         offset = align_to<LEN>(offset);
00207         if (L4_UNLIKELY(!check_size<LEN>(offset, limit)))
00208             return -L4_MSGTOOLONG;
00209         *reinterpret_cast<LEN*>(msg + offset) = a.length;
00210         offset = align_to<A>(offset + sizeof(LEN));
00211         if (L4_UNLIKELY(!check_size<A>(offset, limit, a.length)))
00212             return -L4_MSGTOOLONG;
00213         typedef typename L4::Types::Remove_const<A>::type elem_type;
00214         elem_type *data = reinterpret_cast<elem_type*>(msg + offset);
00215
00216         // we do not correctly handle overlaps
00217         if (!REF || data != a.data)
00218         {
00219             for (LEN i = 0; i < a.length; ++i)
00220                 data[i] = a.data[i];
00221         }
00222
00223         return offset + a.length * sizeof(A);
00224     }
00225 };
00226 } // namespace Detail
00227
00228 template<typename A, typename LEN>

```

```

00229 struct Clnt_val_ops<Array<A, LEN>, Dir_in, Cls_data> :
00230     Detail::Clnt_val_ops_d_in<A, LEN, Array<A, LEN>, false> {};
00231
00232 template<typename A, typename LEN>
00233 struct Clnt_val_ops<Array_ref<A, LEN>, Dir_in, Cls_data> :
00234     Detail::Clnt_val_ops_d_in<A, LEN, Array_ref<A, LEN>, true> {};
00235
00236 template<typename A, typename LEN, typename CLASS>
00237 struct Svr_val_ops<Array_ref<A, LEN>, Dir_in, CLASS> >
00238 : Svr_noops<Array_ref<A, LEN> >
00239 {
00240     typedef Array_ref<A, LEN> svr_type;
00241
00242     using Svr_noops<svr_type>::to_svr;
00243     static int to_svr(char *msg, unsigned offset, unsigned limit,
00244         svr_type &a, Dir_in, Cls_data)
00245     {
00246         offset = align_to<LEN>(offset);
00247         if (L4_UNLIKELY(!check_size<LEN>(offset, limit)))
00248             return -L4_EMSGTOOSHORT;
00249         a.length = *reinterpret_cast<LEN*>(msg + offset);
00250         offset = align_to<A>(offset + sizeof(LEN));
00251         if (L4_UNLIKELY(!check_size<A>(offset, limit, a.length)))
00252             return -L4_EMSGTOOSHORT;
00253         a.data = reinterpret_cast<A*>(msg + offset);
00254         return offset + a.length * sizeof(A);
00255     }
00256 };
00257
00258 template<typename A, typename LEN>
00259 struct Svr_xmit<Array<A, LEN> > : Svr_xmit<Array_ref<A, LEN> > {};
00260
00261 template<typename A, typename LEN>
00262 struct Clnt_val_ops<Array<A, LEN>, Dir_out, Cls_data> : Clnt_noops<Array<A, LEN> >
00263 {
00264     typedef Array<A, LEN> type;
00265
00266     using Clnt_noops<type>::from_msg;
00267     static int from_msg(char *msg, unsigned offset, unsigned limit, long,
00268         type &a, Dir_out, Cls_data)
00269     {
00270         offset = align_to<LEN>(offset);
00271         if (L4_UNLIKELY(!check_size<LEN>(offset, limit)))
00272             return -L4_EMSGTOOSHORT;
00273
00274         LEN l = *reinterpret_cast<LEN*>(msg + offset);
00275
00276         offset = align_to<A>(offset + sizeof(LEN));
00277         if (L4_UNLIKELY(!check_size<A>(offset, limit, l)))
00278             return -L4_EMSGTOOSHORT;
00279
00280         A *data = reinterpret_cast<A*>(msg + offset);
00281
00282         if (l > a.length)
00283             l = a.length;
00284         else
00285             a.length = l;
00286
00287         for (unsigned i = 0; i < l; ++i)
00288             a.data[i] = data[i];
00289
00290         return offset + l * sizeof(A);
00291     };
00292 };
00293
00294 template<typename A, typename LEN>
00295 struct Clnt_val_ops<Array_ref<A, LEN>, Dir_out, Cls_data> :
00296     Clnt_noops<Array_ref<A, LEN> >
00297 {
00298     typedef Array_ref<A, LEN> type;
00299
00300     using Clnt_noops<type>::from_msg;
00301     static int from_msg(char *msg, unsigned offset, unsigned limit, long,
00302         type &a, Dir_out, Cls_data)
00303     {
00304         offset = align_to<LEN>(offset);
00305         if (L4_UNLIKELY(!check_size<LEN>(offset, limit)))
00306             return -L4_EMSGTOOSHORT;
00307
00308         LEN l = *reinterpret_cast<LEN*>(msg + offset);
00309
00310         offset = align_to<A>(offset + sizeof(LEN));
00311         if (L4_UNLIKELY(!check_size<A>(offset, limit, l)))
00312             return -L4_EMSGTOOSHORT;
00313
00314         a.data = reinterpret_cast<A*>(msg + offset);
00315         a.length = l;

```

```

00316     return offset + 1 * sizeof(A);
00317 };
00318 };
00319
00320 template<typename A, typename LEN, typename CLASS>
00321 struct Svr_val_ops<Array_ref<A, LEN>, Dir_out, CLASS> :
00322     Svr_noops<Array_ref<typename L4::Types::Remove_const<A>::type, LEN> &>
00323 {
00324     typedef typename L4::Types::Remove_const<A>::type elem_type;
00325     typedef Array_ref<elem_type, LEN> &svr_type;
00326
00327     using Svr_noops<svr_type>::to_svr;
00328     static int to_svr(char *msg, unsigned offset, unsigned limit,
00329         svr_type a, Dir_out, Cls_data)
00330     {
00331         offset = align_to<LEN>(offset);
00332         if (L4_UNLIKELY(!check_size<LEN>(offset, limit)))
00333             return -L4_MSGTOOLONG;
00334
00335         offset = align_to<A>(offset + sizeof(LEN));
00336         a.data = reinterpret_cast<elem_type *>(msg + offset);
00337         a.length = (limit - offset) / sizeof(A);
00338         return offset;
00339     }
00340
00341     using Svr_noops<svr_type>::from_svr;
00342     static int from_svr(char *msg, unsigned offset, unsigned limit, long,
00343         svr_type a, Dir_out, Cls_data)
00344     {
00345         offset = align_to<LEN>(offset);
00346         if (L4_UNLIKELY(!check_size<LEN>(offset, limit)))
00347             return -L4_MSGTOOLONG;
00348
00349         *reinterpret_cast<LEN *>(msg + offset) = a.length;
00350
00351         offset = align_to<A>(offset + sizeof(LEN));
00352         if (L4_UNLIKELY(!check_size<A>(offset, limit, a.length)))
00353             return -L4_MSGTOOLONG;
00354
00355         return offset + a.length * sizeof(A);
00356     }
00357 };
00358
00359 template<typename A, typename LEN>
00360 struct Svr_xmit<Array<A, LEN> &> : Svr_xmit<Array_ref<A, LEN> &> {};
00361
00362 // Pointer to array is not implemented.
00363 template<typename A, typename LEN>
00364 struct Is_valid_rpc_type<Array_ref<A, LEN> *> : L4::Types::False {};
00365
00366 // Optional input arrays are not implemented.
00367 template<typename A, typename LEN>
00368 struct Is_valid_rpc_type<Opt<Array_ref<A, LEN> > > : L4::Types::False {};
00369
00370 } // namespace Msg
00371
00372 }
```

## 16.470 ipc\_basics

```

00001 // vi:set ft=c++: -- Mode: C++ --
00002 /*
00003  * (c) 2014 Alexander Warg <alexander.warg@kernkonzept.com>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007 #pragma once
00008
00009 #include "types"
00010 #include <l4/sys/utcb.h>
00011 #include <l4/sys/err.h>
00012
00013 namespace L4 {
00014
00015     namespace Ipc {
00016
00017         namespace Msg {
00018
00019             using L4::Types::True;
00020             using L4::Types::False;
00021
00022             constexpr unsigned long align_to(unsigned long bytes, unsigned long align) noexcept
00023             { return (bytes + align - 1) & ~(align - 1); }
00024
```

```

00032
00039 template<typename T>
00040 constexpr unsigned long align_to(unsigned long bytes) noexcept
00041 { return align_to(bytes, __alignof(T)); }
00042
00052 template<typename T>
00053 constexpr bool check_size(unsigned offset, unsigned limit) noexcept
00054 {
00055     return offset + sizeof(T) <= limit;
00056 }
00057
00070 template<typename T, typename CTYPE>
00071 inline bool check_size(unsigned offset, unsigned limit, CTYPE cnt) noexcept
00072 {
00073     if (L4_UNLIKELY(sizeof(CTYPE) <= sizeof(unsigned) &&
00074         ~0U / sizeof(T) <= static_cast<unsigned>(cnt)))
00075         return false;
00076
00077     if (L4_UNLIKELY(sizeof(CTYPE) > sizeof(unsigned) &&
00078         static_cast<CTYPE>(~0U / sizeof(T)) <= cnt))
00079         return false;
00080
00081     return sizeof(T) * cnt <= limit - offset;
00082 }
00083
00084
00085 enum
00086 {
00088     Word_bytes = sizeof(l4_umword_t),
00090     Item_words = 2,
00092     Item_bytes = Word_bytes * Item_words,
00094     Mr_words = L4_UTCB_GENERIC_DATA_SIZE,
00096     Mr_bytes = Word_bytes * Mr_words,
00098     Br_bytes = Word_bytes * L4_UTCB_GENERIC_BUFFERS_SIZE,
00099 };
00100
00101
00113 template<typename T>
00114 inline int msg_add(char *msg, unsigned offs, unsigned limit, T v) noexcept
00115 {
00116     offs = align_to<T>(offs);
00117     if (L4_UNLIKELY(!check_size<T>(offs, limit)))
00118         return -L4_EMMSGTOOLONG;
00119     *reinterpret_cast<typename L4::Types::Remove_const<T>::type *>(msg + offs) = v;
00120     return offs + sizeof(T);
00121 }
00122
00134 template<typename T>
00135 inline int msg_get(char *msg, unsigned offs, unsigned limit, T &v) noexcept
00136 {
00137     offs = align_to<T>(offs);
00138     if (L4_UNLIKELY(!check_size<T>(offs, limit)))
00139         return -L4_EMMSGTOOSHORT;
00140     v = *reinterpret_cast<T *>(msg + offs);
00141     return offs + sizeof(T);
00142 }
00143
00145 struct Dir_in { typedef Dir_in type; typedef Dir_in dir; };
00147 struct Dir_out { typedef Dir_out type; typedef Dir_out dir; };
00148
00150 struct Cls_data { typedef Cls_data type; typedef Cls_data cls; };
00152 struct Cls_item { typedef Cls_item type; typedef Cls_item cls; };
00154 struct Cls_buffer { typedef Cls_buffer type; typedef Cls_buffer cls; };
00155
00156 // Typical combinations
00158 struct Do_in_data : Dir_in, Cls_data {};
00160 struct Do_out_data : Dir_out, Cls_data {};
00162 struct Do_in_items : Dir_in, Cls_item {};
00164 struct Do_out_items : Dir_out, Cls_item {};
00166 struct Do_rcv_buffers : Dir_in, Cls_buffer {};
00167
00168 // implementation details
00169 namespace Detail {
00170
00171 template<typename T> struct _Plain
00172 {
00173     typedef T type;
00174     static T deref(T v) noexcept { return v; }
00175 };
00176
00177 template<typename T> struct _Plain<T *>
00178 {
00179     typedef T type;
00180     static T &deref(T *v) noexcept { return *v; }
00181 };
00182
00183 template<typename T> struct _Plain<T &>

```



```

00184 {
00185     typedef T type;
00186     static T &deref(T &v) noexcept { return v; }
00187 };
00188 };
00189
00190 template<typename T> struct _Plain<T const &>
00191 {
00192     typedef T type;
00193     static T const &deref(T const &v) noexcept { return v; }
00194 };
00195
00196 template<typename T> struct _Plain<T const *>
00197 {
00198     typedef T type;
00199     static T const &deref(T const *v) noexcept { return *v; }
00200 };
00201 };
00202
00210 template<typename MTYPE, typename DIR, typename CLASS> struct Clnt_val_ops;
00211
00212 template<typename T> struct Clnt_noops
00213 {
00214     template<typename A, typename B>
00215     static constexpr int to_msg(char *, unsigned offset, unsigned, T, A, B) noexcept
00216     { return offset; }
00217
00219     template<typename A, typename B>
00220     static constexpr int from_msg(char *, unsigned offset, unsigned, long, T const &, A, B) noexcept
00221     { return offset; }
00222 };
00223
00224 template<typename T> struct Svr_noops
00225 {
00226     template<typename A, typename B>
00227     static constexpr int from_svr(char *, unsigned offset, unsigned, long, T, A, B) noexcept
00228     { return offset; }
00229
00231     template<typename A, typename B>
00232     static constexpr int to_svr(char *, unsigned offset, unsigned, T, A, B) noexcept
00233     { return offset; }
00234 };
00235
00236 template<typename MTYPE, typename CLASS>
00237 struct Clnt_val_ops<MTYPE, Dir_in, CLASS> : Clnt_noops<MTYPE>
00238 {
00239     using Clnt_noops<MTYPE>::to_msg;
00241     static int to_msg(char *msg, unsigned offset, unsigned limit,
00242                     MTYPE arg, Dir_in, CLASS) noexcept
00243     { return msg_add<MTYPE>(msg, offset, limit, arg); }
00244 };
00245
00246
00247 template<typename MTYPE, typename CLASS>
00248 struct Clnt_val_ops<MTYPE, Dir_out, CLASS> : Clnt_noops<MTYPE>
00249 {
00250     using Clnt_noops<MTYPE>::from_msg;
00252     static int from_msg(char *msg, unsigned offset, unsigned limit, long,
00253                       MTYPE &arg, Dir_out, CLASS) noexcept
00254     { return msg_get<MTYPE>(msg, offset, limit, arg); }
00255 };
00256
00264 template<typename MTYPE, typename DIR, typename CLASS> struct Svr_val_ops;
00265
00266 template<typename MTYPE, typename CLASS>
00267 struct Svr_val_ops<MTYPE, Dir_in, CLASS> : Svr_noops<MTYPE>
00268 {
00269     using Svr_noops<MTYPE>::to_svr;
00271     static int to_svr(char *msg, unsigned offset, unsigned limit,
00272                     MTYPE &arg, Dir_in, CLASS) noexcept
00273     { return msg_get<MTYPE>(msg, offset, limit, arg); }
00274 };
00275
00276 template<typename MTYPE, typename CLASS>
00277 struct Svr_val_ops<MTYPE, Dir_out, CLASS> : Svr_noops<MTYPE>
00278 {
00279     using Svr_noops<MTYPE>::to_svr;
00280     static int to_svr(char *, unsigned offs, unsigned limit,
00281                     MTYPE &, Dir_out, CLASS) noexcept
00282     {
00283         offs = align_to<MTYPE>(offs);
00284         if (L4_UNLIKELY(!check_size<MTYPE>(offs, limit)))
00285             return -L4_EMSTOOLONG;
00286         return offs + sizeof(MTYPE);
00287     }
00288
00289     using Svr_noops<MTYPE>::from_svr;

```

```

00291     static int from_svr(char *msg, unsigned offset, unsigned limit, long,
00292                         MTYPE arg, Dir_out, CLASS) noexcept
00293     { return msg_add<MTYPE>(msg, offset, limit, arg); }
00294 };
00295
00296 template<typename T> struct Elem
00297 {
00298     typedef T arg_type;
00299     typedef T svr_type;
00300     typedef T svr_arg_type; // might by const & (depending on the size)
00301
00302     enum { Is_optional = false };
00303 };
00304
00305 template<typename T> struct Elem<T &>
00306 {
00307     typedef T &arg_type;
00308     typedef T svr_type;
00309     typedef T &svr_arg_type;
00310     enum { Is_optional = false };
00311 };
00312
00313 template<typename T> struct Elem<T const &>
00314 {
00315     typedef T const &arg_type;
00316     typedef T svr_type;
00317     // as the RPC uses a const reference we use it here too,
00318     // we could also use pass by value depending on the size
00319     typedef T const &svr_arg_type;
00320     enum { Is_optional = false };
00321 };
00322
00323 template<typename T> struct Elem<T *> : Elem<T &>
00324 {
00325     typedef T *arg_type;
00326 };
00327
00328 template<typename T> struct Elem<T const *> : Elem<T const &>
00329 {
00330     typedef T const *arg_type;
00331 };
00332
00333 template<typename T> struct Elem<T const *> : Elem<T const &>
00334 {
00335     typedef T const *arg_type;
00336 };
00337
00338 template<typename T> struct Is_valid_rpc_type : L4::Types::True {};
00339
00340 // Static assertions outside functions work only properly from C++11
00341 // onwards. On earlier version make sure the compiler fails on an ugly
00342 // undefined struct instead.
00343 template<typename T, bool B> struct Error_invalid_rpc_parameter_used;
00344 template<typename T> struct Error_invalid_rpc_parameter_used<T, true> {};
00345
00346 #if __cplusplus >= 201103L
00347 template<typename T>
00348 struct _Elem : Elem<T>
00349 {
00350     static_assert(Is_valid_rpc_type<T>::value,
00351                 "L4::ipc::Msg::_Elem<T>: type T is not a valid RPC parameter type.");
00352 };
00353 #else
00354 template<typename T>
00355 struct _Elem : Elem<T>,
00356               Error_invalid_rpc_parameter_used<T, Is_valid_rpc_type<T>::value>
00357 {};
00358 #endif
00359
00360
00361 template<typename T> struct Class : Cls_data {};
00362 template<typename T> struct Direction : Dir_in {};
00363 template<typename T> struct Direction<T const &> : Dir_in {};
00364 template<typename T> struct Direction<T const *> : Dir_in {};
00365 template<typename T> struct Direction<T &> : Dir_out {};
00366 template<typename T> struct Direction<T *> : Dir_out {};
00367
00368 template<typename T> struct _Clnt_noops :
00369     Clnt_noops<typename Detail::_Plain<typename _Elem<T>::arg_type>::type>
00370 {};
00371
00372 namespace Detail {
00373
00374     template<typename T, typename DIR, typename CLASS>
00375     struct _Clnt_val_ops :
00376         Clnt_val_ops<typename Detail::_Plain<T>::type, DIR, CLASS> {};
00377
00378     template<typename T,
00379             typename ELEM = _Elem<T>,
00380             typename CLNT_OPS = _Clnt_val_ops<typename ELEM::arg_type,
00381                                             typename Direction<T>::type,

```

```

00383                                     typename Class<typename Detail::_Plain<T>::type>::type>
00384                                     >
00385 struct _Clnt_xmit : CLNT_OPS {};
00386
00387 template<typename T,
00388         typename ELEM = _Elem<T>,
00389         typename SVR_OPS = Svr_val_ops<typename ELEM::svr_type,
00390         typename Direction<T>::type,
00391         typename Class<typename Detail::_Plain<T>::type>::type>
00392         >
00393 struct _Svr_xmit : SVR_OPS {};
00394
00395 } //namespace Detail
00396 template<typename T> struct Clnt_xmit : Detail::_Clnt_xmit<T> {};
00397 template<typename T> struct Svr_xmit : Detail::_Svr_xmit<T> {};
00398
00399 }}} // namespace Msg, Ipc, L4
00400
00401

```


## 16.471 I4/sys/cxx/ipc\_client File Reference

```

#include <l4/sys/cxx/ipc_basics>
#include <l4/sys/cxx/ipc_types>
#include <l4/sys/cxx/ipc_iface>
#include <l4/sys/__typeinfo.h>
#include <l4/sys/err.h>

```

Include dependency graph for ipc\_client:





<i>name</i>	The fully qualified method name to be implemented, this means <code>class::method</code> .
-------------	--

This macro generates the definition (implementation) for the given RPC interface method.

Definition at line 32 of file `ipc_client`.

## 16.472 ipc\_client

[Go to the documentation of this file.](#)

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00002 /*
00003  * (c) 2014 Alexander Warg <alexander.warg@kernkonzept.com>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007 #pragma once
00008 #pragma GCC system_header
00009
00010 #include <l4/sys/cxx/ipc_basics>
00011 #include <l4/sys/cxx/ipc_types>
00012 #include <l4/sys/cxx/ipc_iface>
00013 #include <l4/sys/__typeinfo.h>
00014 #include <l4/sys/err.h>
00015
00019
00020 namespace L4 { namespace Ipc { namespace Msg {
00021 //-----
00022
00032 #define L4_RPC_DEF(name) \
00033     template struct L4::Ipc::Msg::Rpc_call \
00034         <name##_t, name##_t::class_type, name##_t::ipc_type, name##_t::flags_type>
00035
00036
00038 //-----
00039 //Implementation of the RPC call
00040 template<typename OP, typename C, typename FLAGS, typename R, typename ...ARGS>
00041 R L4_EXPORT
00042 Rpc_call<OP, C, R (ARGS...), FLAGS>::
00043     call(L4::Cap<C> cap, typename _Elem<ARGS>::arg_type ...a, l4_utcb_t *utcb) noexcept
00044 {
00045     return Rpc_inline_call<OP, C, R (ARGS...), FLAGS>::call(cap, a..., utcb);
00046 }
00047
00048
00049 } // namespace Msg
00050 } // namespace Ipc
00051 } // namespace L4
00052

```

## 16.473 ipc\_epiface

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00002 /*
00003  * (c) 2014-2015 Alexander Warg <alexander.warg@kernkonzept.com>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007 #pragma once
00008 #pragma GCC system_header
00009
00010 #include "capability.h"
00011 #include "ipc_server"
00012 #include "ipc_string"
00013 #include <l4/sys/types.h>
00014 #include <l4/sys/utcb.h>
00015 #include <l4/sys/__typeinfo.h>
00016 #include <l4/sys/meta>
00017 #include <l4/cxx/type_traits>
00018
00019 namespace L4 {
00020
00021 // forward for Irqep_t
00022 class Irq;

```

```

00023 class Rcv_endpoint;
00024
00025 namespace Ipc_svr {
00026
00027 class Timeout;
00028
00036 class Server_iface
00037 {
00038 private:
00039     Server_iface(Server_iface const &);
00040     Server_iface const &operator = (Server_iface const &);
00041
00042 public:
00044     typedef L4::Type_info::Demand Demand;
00045
00046     Server_iface(Server_iface &&) = delete;
00047     Server_iface &operator = (Server_iface &&) = delete;
00048
00050     Server_iface() {}
00051
00052     // Destroy the server interface
00053     virtual ~Server_iface() = 0;
00054
00064     virtual int alloc_buffer_demand(Demand const &demand) = 0;
00065
00074     virtual L4::Cap<void> get_rcv_cap(int index) const = 0;
00075
00084     virtual int realloc_rcv_cap(int index) = 0;
00085
00093     virtual int add_timeout(Timeout *timeout, l4_kernel_clock_t time) = 0;
00094
00100     virtual int remove_timeout(Timeout *timeout) = 0;
00101
00113     template<typename T>
00114     L4::Cap<T> rcv_cap(int index) const
00115     { return L4::cap_cast<T>(get_rcv_cap(index)); }
00116
00126     L4::Cap<void> rcv_cap(int index) const
00127     { return get_rcv_cap(index); }
00128 };
00129
00130 inline Server_iface::~Server_iface() {}
00131
00132 } // namespace Ipc_svr
00133
00145 struct Epiface
00146 {
00147     Epiface(Epiface const &) = delete;
00148     Epiface &operator = (Epiface const &) = delete;
00149
00151     typedef Ipc_svr::Server_iface Server_iface;
00153     typedef Ipc_svr::Server_iface::Demand Demand;
00154
00155     class Stored_cap : public Cap<void>
00156     {
00157     private:
00158         enum { Managed = 0x10 };
00159
00160     public:
00161         Stored_cap() = default;
00162         Stored_cap(Cap<void> const &c, bool managed = false)
00163             : Cap<void>((c.cap() & L4_CAP_MASK) | (managed ? Managed : 0))
00164         {
00165             static_assert (!(L4_CAP_MASK & Managed), "conflicting bits used...");
00166         }
00167
00168         bool managed() const { return cap() & Managed; }
00169     };
00170
00172     Epiface() : _data(0) {}
00173
00186     virtual l4_msgtag_t dispatch(l4_msgtag_t tag, unsigned rights,
00187                                 l4_utcb_t *utcb) = 0;
00188
00195     virtual Demand get_buffer_demand() const = 0; //{ return Demand(0); }
00196
00198     virtual ~Epiface() = 0;
00199
00206     Stored_cap obj_cap() const { return _cap; }
00207
00213     Server_iface *server_iface() const { return _data; }
00214
00224     int set_server(Server_iface *srv, Cap<void> cap, bool managed = false)
00225     {
00226         if ((srv && cap) || (!srv && !cap))
00227         {
00228             _data = srv;

```

```

00229         _cap = Stored_cap(cap, managed);
00230         return 0;
00231     }
00232
00233     return -L4_EINVAL;
00234 }
00235
00239 void set_obj_cap(Cap<void> const &cap) { _cap = cap; }
00240
00241 private:
00242     Server_iface *_data;
00243     Stored_cap _cap;
00244 };
00245
00246 inline Epiface::~Epiface() {}
00247
00255 template<typename RPC_IFACE, typename BASE = Epiface>
00256 struct Epiface_t0 : BASE
00257 {
00259     typedef RPC_IFACE Interface;
00260
00262     typename Type_info::Demand get_buffer_demand() const
00263     { return typename Kobject_typeid<RPC_IFACE>::Demand(); }
00264
00269     Cap<RPC_IFACE> obj_cap() const
00270     { return L4::cap_cast<RPC_IFACE>(BASE::obj_cap()); }
00271 };
00272
00280 template<typename Derived, typename BASE = Epiface,
00281         bool = cxx::is_polymorphic<BASE>::value>
00282 struct Irqep_t : Epiface_t0<void, BASE>
00283 {
00284     l4_msgtag_t dispatch(l4_msgtag_t, unsigned, l4_utcb_t *) final
00285     {
00286         static_cast<Derived*>(this)->handle_irq();
00287         return l4_msgtag(-L4_ENOREPLY, 0, 0, 0);
00288     }
00289
00294     Cap<L4::Irq> obj_cap() const
00295     { return L4::cap_cast<L4::Irq>(BASE::obj_cap()); }
00296 };
00297
00298 template<typename Derived, typename BASE>
00299 struct Irqep_t<Derived, BASE, false> : Epiface_t0<void, BASE>
00300 {
00301     l4_msgtag_t dispatch(l4_msgtag_t, unsigned, l4_utcb_t *)
00302     {
00303         static_cast<Derived*>(this)->handle_irq();
00304         return l4_msgtag(-L4_ENOREPLY, 0, 0, 0);
00305     }
00306
00311     Cap<L4::Irq> obj_cap() const
00312     { return L4::cap_cast<L4::Irq>(BASE::obj_cap()); }
00313 };
00314
00322 class Registry_iface
00323 {
00324 public:
00325     virtual ~Registry_iface() = 0;
00326
00339     virtual L4::Cap<void>
00340     register_obj(L4::Epiface *o, char const *service) = 0;
00341
00356     virtual L4::Cap<void>
00357     register_obj(L4::Epiface *o) = 0;
00358
00372     virtual L4::Cap<L4::Irq> register_irq_obj(L4::Epiface *o) = 0;
00373
00386     virtual L4::Cap<L4::Rcv_endpoint>
00387     register_obj(L4::Epiface *o, L4::Cap<L4::Rcv_endpoint> ep) = 0;
00388
00401     virtual void
00402     unregister_obj(L4::Epiface *o, bool unmap = true) = 0;
00403 };
00404
00405 inline Registry_iface::~Registry_iface() {}
00406
00407 namespace Ipc {
00408 namespace Detail {
00409
00410 using namespace L4::Typeid;
00411
00412 template<typename IFACE>
00413 struct Meta_svr
00414 {
00415     l4_ret_t op_num_interfaces(L4::Meta::Rights)
00416     { return 1; }

```

```

00417
00418     l4_ret_t op_interface(L4::Meta::Rights, l4_umword_t ifx, long &proto, L4::Ipc::String<char> &name)
00419     {
00420         if (ifx > 0)
00421             return -L4_ERANGE;
00422         proto = L4::kobject_typeid<IFACE>()->proto();
00423         if (auto *n = L4::kobject_typeid<IFACE>()->name())
00424             name.copy_in(n);
00425
00426         return 0;
00427     }
00428
00429     l4_ret_t op_supports(L4::Meta::Rights, l4_mword_t proto)
00430     { return L4::kobject_typeid<IFACE>()->has_proto(proto); }
00431 };
00432
00433 template<typename IFACE, typename LIST>
00434 struct _Dispatch;
00435
00436 // No match dispatcher found
00437 template<typename IFACE>
00438 struct _Dispatch<IFACE, Iface_list_end>
00439 {
00440     template< typename THIS, typename A1, typename A2 >
00441     static l4_msgtag_t f(THIS *, l4_msgtag_t, A1, A2 &)
00442     { return l4_msgtag(-L4_EBADPROTO, 0, 0, 0); }
00443 };
00444
00445 // call matching p_dispatch() function
00446 template<typename IFACE, typename I, typename LIST >
00447 struct _Dispatch<IFACE, Iface_list<I, LIST> >
00448 {
00449     // special handling for the meta protocol, to avoid 'using' murx
00450     template< typename THIS >
00451     static l4_msgtag_t _f(THIS *, l4_msgtag_t tag, unsigned r,
00452                          l4_utcb_t *utcb, True::type)
00453     {
00454         using L4::Ipc::Msg::dispatch_call;
00455         typedef L4::Meta::Rpc Meta;
00456         typedef Meta_svr<IFACE> Msvr;
00457         return dispatch_call<Meta>(static_cast<Msvr*>(nullptr), utcb, tag, r);
00458     }
00459
00460     // normal dispatch to the op<func> methods of \a self.
00461     template< typename THIS >
00462     static l4_msgtag_t _f(THIS *self, l4_msgtag_t t, unsigned r,
00463                          l4_utcb_t *utcb, False::type)
00464     {
00465         using L4::Ipc::Msg::dispatch_call;
00466         return dispatch_call<typename I::iface_type::Rpc>(self, utcb, t, r);
00467     }
00468
00469     // dispatch function with switch for meta protocol
00470     template< typename THIS >
00471     static l4_msgtag_t f(THIS *self, l4_msgtag_t tag, unsigned r,
00472                        l4_utcb_t *utcb)
00473     {
00474         if (I::Proto == tag.label())
00475             return _f(self, tag, r, utcb,
00476                      Bool<I::Proto == static_cast<long>(L4_PROTO_META)>());
00477
00478         return _Dispatch<IFACE, typename LIST::type>::f(self, tag, r, utcb);
00479     }
00480 };
00481
00482 template<typename IFACE>
00483 struct Dispatch :
00484     _Dispatch<IFACE, typename L4::Kobject_typeid<IFACE>::Iface_list::type>
00485 {};
00486
00487 } // namespace Detail
00488
00489 template<typename EPIFACE>
00490 struct Dispatch : Detail::Dispatch<typename EPIFACE::Interface>
00491 {};
00492
00493 } // namespace Ipc
00494
00495 template<typename Derived, typename IFACE, typename BASE = L4::Epiface,
00496         bool = cxx::is_polymorphic<BASE>::value>
00500 struct Epiface_t : Epiface_t0<IFACE, BASE>
00501 {
00502     l4_msgtag_t
00503     dispatch(l4_msgtag_t tag, unsigned rights, l4_utcb_t *utcb) final
00504     {
00505         typedef Ipc::Dispatch<Derived> Dispatch;
00506         return Dispatch::f(static_cast<Derived*>(this), tag, rights, utcb);
00507     }
00508 };

```



```

00510     }
00511 };
00512
00513 template<typename Derived, typename IFACE, typename BASE>
00514 struct Epiface_t<Derived, IFACE, BASE, false> : Epiface_t0<IFACE, BASE>
00515 {
00516     l4_msgtag_t
00517     dispatch(l4_msgtag_t tag, unsigned rights, l4_utcb_t *utcb)
00518     {
00519         typedef Ipc::Dispatch<Derived> Dispatch;
00520         return Dispatch::f(static_cast<Derived*>(this), tag, rights, utcb);
00521     }
00522 };
00523
00529 class Basic_registry
00530 {
00531 public:
00532     typedef Epiface Value;
00538     static Value *find(l4_umword_t label)
00539     { return reinterpret_cast<Value*>(label & ~3UL); }
00540
00554     static l4_msgtag_t dispatch(l4_msgtag_t tag, l4_umword_t label,
00555                                 l4_utcb_t *utcb)
00556     {
00557         return find(label)->dispatch(tag, label, utcb);
00558     }
00559 };
00560
00561
00562 } // namespace L4

```

## 16.474 l4/sys/cxx/ipc\_iface File Reference


Interface Definition Language.

```

#include <l4/sys/cxx/ipc_basics>
#include <l4/sys/cxx/ipc_types>
#include <l4/sys/__typeinfo.h>

```

Include dependency graph for ipc\_iface:



This graph shows which files directly or indirectly include this file:



## Data Structures

- struct `L4::ipc::Call`  
*RPC attribute for a standard RPC call.*
- struct `L4::ipc::Call_zero_send_timeout`  
*RPC attribute for an RPC call, with zero send timeout.*
- struct `L4::ipc::Call_t< RIGHTS >`  
*RPC attribute for an RPC call with required rights.*
- struct `L4::ipc::Send_only`  
*RPC attribute for a send-only RPC.*

## Namespaces

- namespace [L4](#)  
*L4 low-level kernel interface.*
- namespace [L4::ipc](#)  
*IPC related functionality.*
- namespace [L4::ipc::Msg](#)  
*IPC Message related functionality.*

## Macros

- `#define L4_INLINE_RPC_NF(res, name, args...)`  
*Define an inline RPC call type (the type only, no callable).*
- `#define L4_INLINE_RPC_NF_OP(op, res, name, args...)`  
*Define an inline RPC call type with specific opcode (the type only, no callable).*
- `#define L4_INLINE_RPC(res, name, args, attr...)`  
*Define an inline RPC call (type and callable).*
- `#define L4_INLINE_RPC_OP(op, res, name, args, attr...)`  
*Define an inline RPC call with specific opcode (type and callable).*
- `#define L4_RPC_NF(res, name, args...)`  
*Define an RPC call type (the type only, no callable).*
- `#define L4_RPC_NF_OP(op, res, name, args...)`  
*Define an RPC call type with specific opcode (the type only, no callable).*
- `#define L4_RPC(res, name, args, attr...)`  
*Define an RPC call (type and callable).*
- `#define L4_RPC_OP(op, res, name, args, attr...)`  
*Define an RPC call with specific opcode (type and callable).*

## 16.474.1 Detailed Description

Interface Definition Language.

See also

[L4\\_RPC](#), [L4\\_INLINE\\_RPC](#), [L4::ipc::Call](#) [L4::ipc::Send\\_only](#), [L4::ipc::Msg::Rpc\\_call](#), [L4::ipc::Msg::Rpc\\_↔  
inline\\_call](#)

Definition in file [ipc\\_iface](#).

## 16.474.2 Macro Definition Documentation

### 16.474.2.1 L4\_INLINE\_RPC

```
#define L4_INLINE_RPC(
    res,
    name,
    args,
    attr...)

```

#### Value:

`res name args`

Define an inline RPC call (type and callable).

#### Parameters

<i>res</i>	The result type of the RPC call
<i>name</i>	The name of the function ( <code>name_t</code> is used for the type.)
<i>args</i>	The argument list of the RPC function.
<i>attr</i>	Optional RPC attributes ( <a href="#">L4::Ipc::Call</a> , <a href="#">L4::Ipc::Call_t</a> etc.).

#### Examples

[examples/clntsrv/src/shared.h](#).

Definition at line [483](#) of file [ipc\\_iface](#).

Referenced by [L4Re::Mem\\_alloc::info\(\)](#).

### 16.474.2.2 L4\_INLINE\_RPC\_NF

```
#define L4_INLINE_RPC_NF(
    res,
    name,
    args...)

```

#### Value:

```
struct name##_t : L4::Ipc::Msg::Rpc_inline_call<name##_t, Class, res args> \
{ \
    typedef L4::Ipc::Msg::Rpc_inline_call<name##_t, Class, res args> type; \
    L4_INLINE_RPC_SRV_FORWARD(name); \
}

```

Define an inline RPC call type (the type only, no callable).

#### Parameters

<i>res</i>	The result type of the RPC call
<i>name</i>	The name of the function ( <code>name_t</code> is used for the type.)
<i>args</i>	The argument list of the RPC function, and RPC attributes ( <a href="#">L4::Ipc::Call</a> , <a href="#">L4::Ipc::Call_t</a> etc.).

Stubs generated by this macro can be used explicitly in custom wrapper methods that need to use the underlying RPC code and provide some higher level abstraction, for example with default arguments or extra argument conversion.

Definition at line [454](#) of file [ipc\\_iface](#).

**16.474.2.3 L4\_INLINE\_RPC\_NF\_OP**

```
#define L4_INLINE_RPC_NF_OP (
    op,
    res,
    name,
    args...)

```

**Value:**

```
struct name##_t : L4::Ipc::Msg::Rpc_inline_call<name##_t, Class, res args> \
{ \
    typedef L4::Ipc::Msg::Rpc_inline_call<name##_t, Class, res args> type; \
    enum { Opcode = (op) }; \
    L4_INLINE_RPC_SRV_FORWARD(name); \
}

```

Define an inline RPC call type with specific opcode (the type only, no callable).

**Parameters**

<i>op</i>	The opcode number for this function
<i>res</i>	The result type of the RPC call
<i>name</i>	The name of the function ( <i>name_t</i> is used for the type.)
<i>args</i>	The argument list of the RPC function, and RPC attributes ( <a href="#">L4::Ipc::Call</a> , <a href="#">L4::Ipc::Call_t</a> etc.).

Stubs generated by this macro can be used explicitly in custom wrapper methods that need to use the underlying RPC code and provide some higher level abstraction, for example with default arguments or extra argument conversion.

Definition at line [467](#) of file [ipc\\_iface](#).

**16.474.2.4 L4\_INLINE\_RPC\_OP**

```
#define L4_INLINE_RPC_OP (
    op,
    res,
    name,
    args,
    attr...)

```

**Value:**

```
res name args
```

Define an inline RPC call with specific opcode (type and callable).

**Parameters**

<i>op</i>	The opcode number for this function
<i>res</i>	The result type of the RPC call
<i>name</i>	The name of the function ( <i>name_t</i> is used for the type.)
<i>args</i>	The argument list of the RPC function.
<i>attr</i>	Optional RPC attributes ( <a href="#">L4::Ipc::Call</a> , <a href="#">L4::Ipc::Call_t</a> etc.).

Definition at line [498](#) of file [ipc\\_iface](#).

### 16.474.2.5 L4\_RPC

```
#define L4_RPC(
    res,
    name,
    args,
    attr...)

```

#### Value:

res name args

Define an RPC call (type and callable).

#### Parameters

<i>res</i>	The result type of the RPC call
<i>name</i>	The name of the function ( <code>name_t</code> is used for the type.)
<i>args</i>	The argument list of the RPC function.
<i>attr</i>	Optional RPC attributes ( <a href="#">L4::lpc::Call</a> , <a href="#">L4::lpc::Call_t</a> etc.).

Definition at line 542 of file [ipc\\_iface](#).

Referenced by [L4Re::Dataspace::info\(\)](#).

### 16.474.2.6 L4\_RPC\_NF

```
#define L4_RPC_NF(
    res,
    name,
    args...)

```

#### Value:

```
struct name##_t : L4::Ipc::Msg::Rpc_call<name##_t, Class, res args>
{
    typedef L4::Ipc::Msg::Rpc_call<name##_t, Class, res args> type;
    L4_INLINE_RPC_SRV_FORWARD(name);
}

```

Define an RPC call type (the type only, no callable).

#### Parameters

<i>res</i>	The result type of the RPC call
<i>name</i>	The name of the function ( <code>name_t</code> is used for the type.)
<i>args</i>	The argument list of the RPC function, and RPC attributes ( <a href="#">L4::lpc::Call</a> , <a href="#">L4::lpc::Call_t</a> etc.).

Definition at line 511 of file [ipc\\_iface](#).

Referenced by [L4Re::Dataspace::info\(\)](#).

**16.474.2.7 L4\_RPC\_NF\_OP**

```
#define L4_RPC_NF_OP (
    op,
    res,
    name,
    args...)

```

**Value:**

```
struct name##_t : L4::Ipc::Msg::Rpc_call<name##_t, Class, res args>
{
    typedef L4::Ipc::Msg::Rpc_call<name##_t, Class, res args> type;
    enum { Opcode = (op) };
    L4_INLINE_RPC_SRV_FORWARD(name);
}

```

```
\\
\\
\\
\\

```

Define an RPC call type with specific opcode (the type only, no callable).

**Parameters**

<i>op</i>	The opcode number for this function
<i>res</i>	The result type of the RPC call
<i>name</i>	The name of the function ( <i>name_t</i> is used for the type.)
<i>args</i>	The argument list of the RPC function, and RPC attributes ( <a href="#">L4::Ipc::Call</a> , <a href="#">L4::Ipc::Call_t</a> etc.).

Definition at line 526 of file [ipc\\_iface](#).

**16.474.2.8 L4\_RPC\_OP**

```
#define L4_RPC_OP (
    op,
    res,
    name,
    args,
    attr...)

```

**Value:**

```
res name args
```

Define an RPC call with specific opcode (type and callable).

**Parameters**

<i>op</i>	The opcode number for this function
<i>res</i>	The result type of the RPC call
<i>name</i>	The name of the function ( <i>name_t</i> is used for the type.)
<i>args</i>	The argument list of the RPC function.
<i>attr</i>	Optional RPC attributes ( <a href="#">L4::Ipc::Call</a> , <a href="#">L4::Ipc::Call_t</a> etc.).

Definition at line 557 of file [ipc\\_iface](#).

## 16.475 ipc\_iface

[Go to the documentation of this file.](#)

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00002 /*
00003  * (c) 2014 Alexander Warg <alexander.warg@kernkonzept.com>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007 #pragma once
00008 #pragma GCC system_header
00009
00010 #include <l4/sys/cxx/ipc_basics>
00011 #include <l4/sys/cxx/ipc_types>
00012 #include <l4/sys/__typeinfo.h>
00013
00022
00219
00220 // TODO: add some more documentation
00221 namespace L4 { namespace Ipc {
00222
00239 struct L4_EXPORT Call
00240 {
00241     enum { Is_call = true };
00242     enum { Rights = 0 };
00243     static l4_timeout_t timeout() { return L4_IPC_NEVER; }
00244 };
00245
00249 struct L4_EXPORT Call_zero_send_timeout : Call
00250 {
00251     static l4_timeout_t timeout() { return L4_IPC_SEND_TIMEOUT_0; }
00252 };
00253
00269 template<unsigned RIGHTS>
00270 struct L4_EXPORT Call_t : Call
00271 {
00272     enum { Rights = RIGHTS };
00273 };
00274
00287 struct L4_EXPORT Send_only
00288 {
00289     enum { Is_call = false };
00290     enum { Rights = 0 };
00291     static l4_timeout_t timeout() { return L4_IPC_NEVER; }
00292 };
00293
00294 namespace Msg {
00295
00306 template<typename OP, typename CLASS, typename SIG, typename FLAGS = Call>
00307 struct L4_EXPORT Rpc_inline_call;
00308
00313 template<typename OP, typename CLASS, typename FLAGS, typename R,
00314         typename ...ARGS>
00315 struct L4_EXPORT Rpc_inline_call<OP, CLASS, R (ARGS...), FLAGS>
00316 {
00317     template<typename T> struct Result { typedef T result_type; };
00318     enum
00319     {
00320         Return_tag = L4::Types::Same<R, l4_msgtag_t>::value
00321     };
00322
00324     typedef Rpc_inline_call type;
00326     typedef OP op_type;
00328     typedef CLASS class_type;
00330     typedef typename Result<R>::result_type result_type;
00332     typedef R ipc_type (ARGS...);
00334     typedef result_type func_type (typename _Elem<ARGS>::arg_type...);
00335
00337     typedef FLAGS flags_type;
00338
00339     template<typename RES>
00340     static typename L4::Types::Enable_if< Return_tag, RES >::type
00341     return_err(l4_ret_t err) noexcept { return l4_msgtag(err, 0, 0, 0); }
00342
00343     template<typename RES>
00344     static typename L4::Types::Enable_if< Return_tag, RES >::type
00345     return_ipc_err(l4_msgtag_t tag, l4_utcb_t const *) noexcept { return tag; }
00346
00347     template<typename RES>
00348     static typename L4::Types::Enable_if< Return_tag, RES >::type
00349     return_code(l4_msgtag_t tag) noexcept { return tag; }
00350
00351     template<typename RES>
00352     static typename L4::Types::Enable_if< !Return_tag, RES >::type
00353     return_err(long err) noexcept { return err; }

```



```

00354
00355     template<typename RES>
00356     static typename L4::Types::Enable_if< !Return_tag, RES >::type
00357     return_ipc_err(l4_msgtag_t, l4_utcb_t *utcb) noexcept
00358     { return l4_ipc_to_errno(l4_ipc_error_code(utcb)); }
00359
00360     template<typename RES>
00361     static typename L4::Types::Enable_if< !Return_tag, RES >::type
00362     return_code(l4_msgtag_t tag) noexcept { return tag.label(); }
00363
00364     static R call(L4::Cap<class_type> cap,
00365                  typename _Elem<ARGS>::arg_type ...a,
00366                  l4_utcb_t *utcb = l4_utcb()) noexcept;
00367 };
00368
00373 template<typename OP, typename CLASS, typename SIG, typename FLAGS = Call>
00374 struct L4_EXPORT Rpc_call;
00375
00383 template<typename IPC, typename SIG> struct _Call;
00384
00386 template<typename IPC, typename R, typename ...ARGS>
00387 struct _Call<IPC, R (ARGS...)>
00388 {
00389 public:
00390     typedef typename IPC::class_type class_type;
00391     typedef typename IPC::result_type result_type;
00392
00393 private:
00394     L4::Cap<class_type> cap() const noexcept
00395     {
00396         return L4::Cap<class_type>(reinterpret_cast<l4_cap_idx_t>(this)
00397                                     & L4_CAP_MASK);
00398     }
00399
00400 public:
00402     result_type operator () (ARGS ...a, l4_utcb_t *utcb = l4_utcb()) const noexcept
00403     { return IPC::call(cap(), a..., utcb); }
00404 };
00405
00412 template<typename IPC> struct Call : _Call<IPC, typename IPC::func_type> {};
00413
00418 template<typename OP,
00419           typename CLASS,
00420           typename FLAGS,
00421           typename R,
00422           typename ...ARGS>
00423 struct L4_EXPORT Rpc_call<OP, CLASS, R (ARGS...), FLAGS> :
00424     Rpc_inline_call<OP, CLASS, R (ARGS...), FLAGS>
00425 {
00426     static R call(L4::Cap<CLASS> cap,
00427                  typename _Elem<ARGS>::arg_type ...a,
00428                  l4_utcb_t *utcb = l4_utcb()) noexcept;
00429 };
00430
00431 #define L4_INLINE_RPC_SRV_FORWARD(name)
00432     template<typename OBJ> struct fwd
00433     {
00434         OBJ *o;
00435         fwd(OBJ *o) noexcept : o(o) {}
00436         template<typename ...ARGS>
00437         decltype(auto) call(ARGS ...a) noexcept(noexcept(o->op_##name(a...)))
00438         { return o->op_##name(a...); }
00439     }
00440
00441
00454 #define L4_INLINE_RPC_NF(res, name, args...)
00455     struct name##_t : L4::Ip::Msg::Rpc_inline_call<name##_t, Class, res args>
00456     {
00457         typedef L4::Ip::Msg::Rpc_inline_call<name##_t, Class, res args> type;
00458         L4_INLINE_RPC_SRV_FORWARD(name);
00459     }
00460
00467 #define L4_INLINE_RPC_NF_OP(op, res, name, args...)
00468     struct name##_t : L4::Ip::Msg::Rpc_inline_call<name##_t, Class, res args>
00469     {
00470         typedef L4::Ip::Msg::Rpc_inline_call<name##_t, Class, res args> type;
00471         enum { Opcode = (op) };
00472         L4_INLINE_RPC_SRV_FORWARD(name);
00473     }
00474
00475 #ifndef DOXYGEN
00483 #define L4_INLINE_RPC(res, name, args, attr...) res name args
00484 #else
00485 #define L4_INLINE_RPC(res, name, args...)
00486     L4_INLINE_RPC_NF(res, name, args); L4::Ip::Msg::Call<name##_t> name
00487 #endif
00488

```

```

00489 #ifndef DOXYGEN
00498 #define L4_INLINE_RPC_OP(op, res, name, args, attr...) res name args
00499 #else
00500 #define L4_INLINE_RPC_OP(op, res, name, args...) \
00501     L4_INLINE_RPC_NF_OP(op, res, name, args); L4::Ipc::Msg::Call<name##_t> name
00502 #endif
00503
00511 #define L4_RPC_NF(res, name, args...) \
00512     struct name##_t : L4::Ipc::Msg::Rpc_call<name##_t, Class, res args> \
00513     { \
00514         typedef L4::Ipc::Msg::Rpc_call<name##_t, Class, res args> type; \
00515         L4_INLINE_RPC_SRV_FORWARD(name); \
00516     } \
00517
00526 #define L4_RPC_NF_OP(op, res, name, args...) \
00527     struct name##_t : L4::Ipc::Msg::Rpc_call<name##_t, Class, res args> \
00528     { \
00529         typedef L4::Ipc::Msg::Rpc_call<name##_t, Class, res args> type; \
00530         enum { Opcode = (op) }; \
00531         L4_INLINE_RPC_SRV_FORWARD(name); \
00532     } \
00533
00534 #ifndef DOXYGEN
00542 #define L4_RPC(res, name, args, attr...) res name args
00543 #else
00544 #define L4_RPC(res, name, args...) \
00545     L4_RPC_NF(res, name, args); L4::Ipc::Msg::Call<name##_t> name
00546 #endif
00547
00548 #ifndef DOXYGEN
00557 #define L4_RPC_OP(op, res, name, args, attr...) res name args
00558 #else
00559 #define L4_RPC_OP(op, res, name, args...) \
00560     L4_RPC_NF_OP(op, res, name, args); L4::Ipc::Msg::Call<name##_t> name
00561 #endif
00562
00563
00568 namespace Detail {
00569
00573 template<typename ...ARGS>
00574 struct Buf
00575 {
00576 public:
00577     template<typename DIR>
00578     static constexpr int write(char *, int offset, int) noexcept
00579     { return offset; }
00580
00581     template<typename DIR>
00582     static constexpr int read(char *, int offset, int, l4_ret_t) noexcept
00583     { return offset; }
00584
00585     typedef void Base;
00586 };
00587
00588 template<typename A, typename ...M>
00589 struct Buf<A, M...> : Buf<M...>
00590 {
00591     typedef Buf<M...> Base;
00592
00593     typedef Clnt_xmit<A> xmit;
00594     typedef typename _Elem<A>::arg_type arg_type;
00595     typedef Detail::_Plain<arg_type> plain;
00596
00597     template<typename DIR>
00598     static int
00599     write(char *base, int offset, int limit,
00600           arg_type a, typename _Elem<M>::arg_type ...m) noexcept
00601     {
00602         offset = xmit::to_msg(base, offset, limit, plain::deref(a),
00603                               typename DIR::dir(), typename DIR::cls());
00604         return Base::template write<DIR>(base, offset, limit, m...);
00605     }
00606
00607     template<typename DIR>
00608     static int
00609     read(char *base, int offset, int limit, l4_ret_t ret,
00610          arg_type a, typename _Elem<M>::arg_type ...m) noexcept
00611     {
00612         int r = xmit::from_msg(base, offset, limit, ret, plain::deref(a),
00613                                typename DIR::dir(), typename DIR::cls());
00614         if (L4_LIKELY(r >= 0))
00615             return Base::template read<DIR>(base, r, limit, ret, m...);
00616
00617         if (_Elem<A>::Is_optional)
00618             return Base::template read<DIR>(base, offset, limit, ret, m...);
00619
00620         return r;

```

```

00621     }
00622 };
00623
00624 template <typename ...ARGS> struct _Part
00625 {
00626     typedef Buf<ARGS...> Data;
00627
00628     template<typename DIR>
00629     static int write(void *b, int offset, int limit,
00630                     typename _Elem<ARGS>::arg_type ...m) noexcept
00631     {
00632         char *buf = static_cast<char *>(b);
00633         int r = Data::template write<DIR>(buf, offset, limit, m...);
00634         if (L4_LIKELY(r >= offset))
00635             return r - offset;
00636         return r;
00637     }
00638 }
00639
00640 template<typename DIR>
00641 static int read(void *b, int offset, int limit, l4_ret_t ret,
00642                typename _Elem<ARGS>::arg_type ...m) noexcept
00643 {
00644     char *buf = static_cast<char *>(b);
00645     int r = Data::template read<DIR>(buf, offset, limit, ret, m...);
00646     if (L4_LIKELY(r >= offset))
00647         return r - offset;
00648     return r;
00649 }
00650 };
00651
00652 template<typename IPC_TYPE, typename OPCODE = void>
00653 struct Part;
00654
00655 // The version without an op-code
00656 template<typename R, typename ...ARGS>
00657 struct Part<R (ARGS...), void> : _Part<ARGS...>
00658 {
00659     typedef Buf<ARGS...> Data;
00660
00661     // write arguments, skipping the dummy opcode
00662     template<typename DIR>
00663     static int write_op(void *b, int offset, int limit,
00664                        int /*placeholder for op*/,
00665                        typename _Elem<ARGS>::arg_type ...m) noexcept
00666     {
00667         char *buf = static_cast<char *>(b);
00668         int r = Data::template write<DIR>(buf, offset, limit, m...);
00669         if (L4_LIKELY(r >= offset))
00670             return r - offset;
00671         return r;
00672     }
00673 }
00674 };
00675
00676 // Message part with additional opcode
00677 template<typename OPCODE, typename R, typename ...ARGS>
00678 struct Part<R (ARGS...), OPCODE> : _Part<ARGS...>
00679 {
00680     typedef OPCODE opcode_type;
00681     typedef Buf<opcode_type, ARGS...> Data;
00682
00683     // write arguments, including the opcode
00684     template<typename DIR>
00685     static int write_op(void *b, int offset, int limit,
00686                        opcode_type op, typename _Elem<ARGS>::arg_type ...m) noexcept
00687     {
00688         char *buf = static_cast<char *>(b);
00689         int r = Data::template write<DIR>(buf, offset, limit, op, m...);
00690         if (L4_LIKELY(r >= offset))
00691             return r - offset;
00692         return r;
00693     }
00694 }
00695 };
00696
00697 } // namespace Detail
00698
00699 //-----
00700 // Implementation of the RPC call
00701 // TODO: Add support for timeout via special RPC argument
00702 // TODO: Add support for passing the UTCB pointer as argument
00703 //
00704 template<typename OP, typename CLASS, typename FLAGS, typename R,
00705         typename ...ARGS>
00706 inline R
00707 Rpc_inline_call<OP, CLASS, R (ARGS...), FLAGS>::
00708     call(L4::Cap<CLASS> cap,
00709         typename _Elem<ARGS>::arg_type ...a,

```

```

00717         l4_utcb_t *utcb) noexcept
00718 {
00719     using namespace Ipc::Msg;
00720
00721     typedef typename Kobject_typeid<CLASS>::Iface::Rpc Rpcs;
00722     typedef typename Rpcs::template Rpc<OP> Opt;
00723     typedef Detail::Part<ipc_type, typename Rpcs::opcode_type> Args;
00724
00725     l4_msg_regs_t *mrs = l4_utcb_mr_u(utcb);
00726
00727     // handle in-data part of the arguments
00728     int send_bytes =
00729         Args::template write_op<Do_in_data>(mrs->mr, 0, Mr_bytes,
00730                                             Opt::Opcode, a...);
00731
00732     if (L4_UNLIKELY(send_bytes < 0))
00733         return return_err<R>(send_bytes);
00734
00735     send_bytes = align_to<l4_umword_t>(send_bytes);
00736     int const send_words = send_bytes / Word_bytes;
00737     // write the in-items part of the message if there is one
00738     int item_bytes =
00739         Args::template write<Do_in_items>(&mrs->mr[send_words], 0,
00740                                           Mr_bytes - send_bytes, a...);
00741
00742     if (L4_UNLIKELY(item_bytes < 0))
00743         return return_err<R>(item_bytes);
00744
00745     int send_items = item_bytes / Item_bytes;
00746
00747     {
00748         // setup the receive buffers for the RPC call
00749         l4_buf_regs_t *brs = l4_utcb_br_u(utcb);
00750         // XXX: we currently support only one type of receive buffers per call
00751         brs->bdr = 0; // we always start at br[0]
00752
00753         // the limit leaves us at least one register for the zero terminator
00754         // add the buffers given as arguments to the buffer registers
00755         int bytes =
00756             Args::template write<Do_rcv_buffers>(brs->br, 0, Br_bytes - Word_bytes,
00757                                                  a...);
00758
00759         if (L4_UNLIKELY(bytes < 0))
00760             return return_err<R>(bytes);
00761
00762         brs->br[bytes / Word_bytes] = 0;
00763     }
00764
00765     // here we do the actual IPC -----
00766     l4_msgtag_t t;
00767     t = l4_msgtag(CLASS::Protocol, send_words, send_items, 0);
00768     // do the call (Q: do we need support for timeouts?)
00769     if (flags_type::Is_call)
00770         t = l4_ipc_call(cap.cap(), utcb, t, flags_type::timeout());
00771     else
00772     {
00773         t = l4_ipc_send(cap.cap(), utcb, t, flags_type::timeout());
00774         if (L4_UNLIKELY(t.has_error()))
00775             return return_ipc_err<R>(t, utcb);
00776
00777         return return_code<R>(l4_msgtag(0, 0, 0, t.flags()));
00778     }
00779
00780     // unmarshalling starts here -----
00781
00782     // bail out early in the case of an IPC error
00783     if (L4_UNLIKELY(t.has_error()))
00784         return return_ipc_err<R>(t, utcb);
00785
00786     // take the label as return value
00787     l4_ret_t r = t.label();
00788
00789     // bail out on negative error codes too
00790     if (L4_UNLIKELY(r < 0))
00791         return return_err<R>(r);
00792
00793     int const rcv_bytes = t.words() * Word_bytes;
00794
00795     // read the static out-data values to the arguments
00796     int err = Args::template read<Do_out_data>(mrs->mr, 0, rcv_bytes, r, a...);
00797
00798     int const item_limit = t.items() * Item_bytes;
00799
00800     if (L4_UNLIKELY(err < 0 || item_limit > Mr_bytes))
00801         return return_err<R>(-L4_MSGTOOSHORT);
00802
00803

```

```

00804 // read the static out-items to the arguments
00805 err = Args::template read<Do_out_items>(&mrs->mr[t.words()], 0, item_limit,
00806                                         r, a...);
00807
00808 if (L4_UNLIKELY(err < 0))
00809     return return_err<R>(-L4_MSGTOOSHORT);
00810
00811 return return_code<R>(t);
00812 }
00813
00814 } // namespace Msg
00815 } // namespace Ipc
00816 } // namespace L4

```

## 16.476 ipc\_legacy

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00002 /*
00003  * Copyright (C) 2015, 2017, 2024 Kernkonzept GmbH.
00004  * Author(s): Alexander Warg <alexander.warg@kernkonzept.com>
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00008 #pragma once
00009
00010 #include <l4/sys/cxx/ipc_epiface>
00011 #ifndef L4_RPC_DISABLE_LEGACY_DISPATCH
00012 #define L4_RPC_LEGACY_DISPATCH(IFACE)
00013     template<typename IOS>
00014     int dispatch(unsigned rights, IOS &ios)
00015     {
00016         typedef ::L4::Ipc::Detail::Dispatch<IFACE> Dispatch;
00017         l4_msgtag_t r = Dispatch::f(this, ios.tag(), rights, ios.utcb());
00018         ios.set_ipc_params(r);
00019         return r.label();
00020     }
00021
00022     template<typename IOS>
00023     int p_dispatch(IFACE *, unsigned rights, IOS &ios)
00024     {
00025         using ::L4::Ipc::Msg::dispatch_call;
00026         l4_msgtag_t r;
00027         r = dispatch_call<typename IFACE::Rpcs>(this, ios.utcb(),
00028                                                 ios.tag(), rights);
00029         ios.set_ipc_params(r);
00030         return r.label();
00031     }
00032
00033 #define L4_RPC_LEGACY_USING(IFACE) \
00034     using IFACE::p_dispatch
00035
00036 #else
00037 #define L4_RPC_LEGACY_DISPATCH(IFACE)
00038 #define L4_RPC_LEGACY_USING(IFACE)
00039 #endif

```

## 16.477 ipc\_ret\_array

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00002 /*
00003  * (c) 2014 Alexander Warg <alexander.warg@kernkonzept.com>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007 #pragma once
00008
00009 #include "types"
00010 #include "ipc_basics"
00011
00012 namespace L4 { namespace Ipc L4_EXPORT {
00013
00014 // -----
00023 template<typename T> struct L4_EXPORT Ret_array
00024 {
00025     typedef T const **ptr_type;
00026
00027     T *value = nullptr;
00028     unsigned max = 0;

```

```

00029 Ret_array() {}
00030 Ret_array(T *v, unsigned max) : value(v), max(max) {}
00031 };
00032
00033 namespace Msg {
00034
00035 template<typename A> struct Elem< Ret_array<A> >
00036 {
00037     enum { Is_optional = false };
00038     typedef Ret_array<A> type;
00039     typedef typename type::ptr_type arg_type;
00040     typedef type svr_type;
00041     typedef type svr_arg_type;
00042 };
00043
00044 template<typename A>
00045 struct Is_valid_rpc_type<Ret_array<A> *> : L4::Types::False {};
00046 template<typename A>
00047 struct Is_valid_rpc_type<Ret_array<A> &> : L4::Types::False {};
00048 template<typename A>
00049 struct Is_valid_rpc_type<Ret_array<A> const &> : L4::Types::False {};
00050 template<typename A>
00051 struct Is_valid_rpc_type<Ret_array<A> const *> : L4::Types::False {};
00052
00053 template<typename A> struct Class< Ret_array<A> > : Class<A>::type {};
00054 template<typename A> struct Direction< Ret_array<A> > : Dir_out {};
00055
00056 template<typename A, typename CLASS>
00057 struct Clnt_val_ops<A const *, Dir_out, CLASS> : Clnt_noops<A const *>
00058 {
00059     using Clnt_noops<A const *>::from_msg;
00060     static int from_msg(char *msg, unsigned offset, unsigned limit, long ret,
00061         A const *&arg, Dir_out, Cls_data)
00062     {
00063         offset = align_to<A>(offset);
00064         arg = reinterpret_cast<A const *>(msg + offset);
00065         if (L4_UNLIKELY(!check_size<A>(offset, limit, ret)))
00066             return -1;
00067         return offset + ret * sizeof(A);
00068     }
00069 };
00070 };
00071
00072 template<typename A, typename CLASS>
00073 struct Svr_val_ops<Ret_array<A>, Dir_out, CLASS> :
00074     Svr_noops<Ret_array<A> >
00075 {
00076     typedef Ret_array<A> ret_array;
00077     using Svr_noops<ret_array>::from_svr;
00078     static int from_svr(char *, unsigned offset, unsigned limit, long ret,
00079         ret_array const &, Dir_out, CLASS)
00080     {
00081         offset = align_to<A>(offset);
00082         if (L4_UNLIKELY(!check_size<A>(offset, limit, ret)))
00083             return -1;
00084         offset += sizeof(A) * ret;
00085         return offset;
00086     }
00087
00088     using Svr_noops<ret_array>::to_svr;
00089     static int to_svr(char *msg, unsigned offset, unsigned limit,
00090         ret_array &arg, Dir_out, CLASS)
00091     {
00092         // there can be actually no limit check here, as this
00093         // is variably sized output array
00094         // FIXME: we could somehow makesure that this is the last
00095         // output value...
00096         offset = align_to<A>(offset);
00097         arg = ret_array(reinterpret_cast<A*>(msg + offset),
00098             (limit - offset) / sizeof(A));
00099         // FIXME: we dont know the length of the array here so, cheat
00100         return offset;
00101     }
00102 };
00103 } // namespace Msg
00104
00105 }}

```

## 16.478 I4/cxx/ipc\_server File Reference

IPC server loop.

[illegible]

- class `L4::Server_object`  
*Abstract server object to be used with `L4::Server` and `L4::Basic_registry`.*
- struct `L4::Server_object_t< IFACE, BASE >`  
*Base class (template) for server implementing server objects.*
- struct `L4::Server_object_x< Derived, IFACE, BASE >`  
*Helper class to implement p\_dispatch based server objects.*
- struct `L4::Irq_handler_object`  
*Server object base class for handling IRQ messages.*

- namespace **L4**  
*L4 low-level kernel interface.*

Definition in file [ipc\\_server](#).

## 16.479 ipc\_server

[Go to the documentation of this file.](#)

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00006 /*
00007  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00008  *           Alexander Warg <warg@os.inf.tu-dresden.de>,
00009  *           Torsten Frenzel <frenzel@os.inf.tu-dresden.de>
00010  *           economic rights: Technische Universität Dresden (Germany)
00011  *
00012  * License: see LICENSE.spdx (in this directory or the directories above)
00013  */
00014 #pragma once
00015
00016 #include <l4/sys/capability>
00017 #include <l4/sys/typeinfo_svr>
00018 #include <l4/sys/err.h>
00019 #include <l4/cxx/ipc_stream>
00020 #include <l4/sys/cxx/ipc_epiface>
00021 #include <l4/sys/cxx/ipc_server_loop>
00022 #include <l4/cxx/type_traits>
00023 #include <l4/cxx/exceptions>
00024
00025 namespace L4 {
00026
00038 class Server_object : public Epiface
00039 {
00040 public:
00058     virtual int dispatch(unsigned long rights, Ipc::Iostream &ios) = 0;
00059
00060     l4_msgtag_t dispatch(l4_msgtag_t tag, unsigned rights, l4_utcb_t *utcb) override
00061     {
00062         L4::Ipc::Iostream ios(utcb);
00063         ios.tag() = tag;
00064         int r = dispatch(rights, ios);
00065         return ios.prepare_ipc(r);
00066     }
00067
00068     Cap<Kobject> obj_cap() const
00069     { return cap_cast<Kobject>(Epiface::obj_cap()); }
00070 };
00071
00079 template<typename IFACE, typename BASE = L4::Server_object>
00080 struct Server_object_t : BASE
00081 {
00083     typedef IFACE Interface;
00084
00086     typename BASE::Demand get_buffer_demand() const override
00087     { return typename L4::Kobject_typeid<IFACE>::Demand(); }
00088
00099     int dispatch_meta_request(L4::Ipc::Iostream &ios)
00100     { return L4::Util::handle_meta_request<IFACE>(ios); }
00101
00113     template<typename THIS>
00114     static int proto_dispatch(THIS *self, l4_umword_t rights, L4::Ipc::Iostream &ios)
00115     {
00116         l4_msgtag_t t;
00117         ios » t;
00118         return Kobject_typeid<IFACE>::proto_dispatch(self, t.label(), rights, ios);
00119     }
00120 };
00121
00142 template<typename Derived, typename IFACE, typename BASE = L4::Server_object>
00143 struct Server_object_x : Server_object_t<IFACE, BASE>
00144 {
00146     int dispatch(l4_umword_t r, L4::Ipc::Iostream &ios)
00147     {
00148         return Server_object_t<IFACE, BASE>::proto_dispatch(static_cast<Derived *>(this),
00149                                                             r, ios);
00150     }
00151 };
00152
00161 struct Irq_handler_object : Server_object_t<Kobject> {};
00162
00163 }

```

## 16.480 ipc\_server

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00002 /*

```



```

00003  * (c) 2014 Alexander Warg <alexander.warg@kernkonzept.com>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007  #pragma once
00008  #pragma GCC system_header
00009
00010  #include <l4/sys/cxx/ipc_basics>
00011  #include <l4/sys/cxx/ipc_iface>
00012  #include <l4/sys/cxx/limits>
00013  #include <l4/sys/___typeinfo.h>
00014  #include <l4/sys/assert.h>
00015  #include <l4/sys/err.h>
00016  #include <stddef.h>
00017
00018  namespace L4 {
00019  namespace Ipc {
00020  namespace Msg {
00021  namespace Detail {
00022
00023  template<typename T> struct Sizeof { enum { size = sizeof(T) }; };
00024  template<> struct Sizeof<void> { enum { size = 0 }; };
00025
00026  template<typename ...> struct Arg_pack
00027  {
00028      template<typename DIR>
00029      unsigned get(char *, unsigned offset, unsigned)
00030      { return offset; }
00031
00032      template<typename DIR>
00033      unsigned set(char *, unsigned offset, unsigned, l4_ret_t)
00034      { return offset; }
00035
00036      template<typename F, typename ...ARGS>
00037      decltype(auto) call(F f, ARGS ...args)
00038      { return f(args...); }
00039
00040      template<typename O, typename FUNC, typename ...ARGS>
00041      auto obj_call(O *o, ARGS ...args)
00042      -> decltype(typename FUNC::template fwd<O>(o).template call<ARGS...>(args...))
00043      {
00044          typedef typename FUNC::template fwd<O> Fwd;
00045          using Idl_ret = typename FUNC::result_type;
00046          using Svr_ret = decltype(Fwd(o).template call<ARGS...>(args...));
00047          auto ret = Fwd(o).template call<ARGS...>(args...);
00048
00049          using L4::Types::numeric_limits;
00050          // Truncating a negative return value which is too small could result in a
00051          // positive value pretending "success" to the caller.
00052          if constexpr (numeric_limits<Svr_ret>::min() < numeric_limits<Idl_ret>::min())
00053          {
00054              if (L4_UNLIKELY(ret < numeric_limits<Idl_ret>::min()))
00055                  return -L4_MSGERRRANGE;
00056          }
00057          // Truncating a positive return value which is too large results either in a
00058          // positive value different from the original return value (but interpreted
00059          // as "success" by the caller) or in a negative value. Trigger an assertion
00060          // in these cases but also return an error in case of NDEBUG=y.
00061          if constexpr (numeric_limits<Svr_ret>::max() > numeric_limits<Idl_ret>::max())
00062          {
00063              l4_assert(ret <= numeric_limits<Idl_ret>::max());
00064              if (L4_UNLIKELY(ret > numeric_limits<Idl_ret>::max()))
00065                  return -L4_MSGERRRANGE;
00066          }
00067          // The following two checks are required in case the Idl_ret limits exceed
00068          // the limits of the 'label' part of l4_msgtag_t.
00069          if constexpr (numeric_limits<Svr_ret>::min() < numeric_limits<l4_msgtag_t>::min())
00070          {
00071              if (L4_UNLIKELY(ret < numeric_limits<l4_msgtag_t>::min()))
00072                  return -L4_MSGERRRANGE;
00073          }
00074          if constexpr (numeric_limits<Svr_ret>::max() > numeric_limits<l4_msgtag_t>::max())
00075          {
00076              l4_assert(ret <= numeric_limits<l4_msgtag_t>::max());
00077              if (L4_UNLIKELY(ret > numeric_limits<l4_msgtag_t>::max()))
00078                  return -L4_MSGERRRANGE;
00079          }
00080          return ret;
00081      }
00082  };
00083
00084  template<typename T, typename SVR_TYPE, typename ...M>
00085  struct Svr_arg : Svr_xmit<T>, Arg_pack<M...>
00086  {
00087      typedef Arg_pack<M...> Base;
00088  };
00089
00090  template<typename T, typename SVR_TYPE, typename ...M>
00091  struct Svr_arg : Svr_xmit<T>, Arg_pack<M...>
00092  {
00093      typedef Arg_pack<M...> Base;
00094  };
00095

```

```

00096 typedef SVR_TYPE svr_type;
00097 typedef typename _Elem<T>::svr_arg_type svr_arg_type;
00098
00099 svr_type v;
00100
00101 template<typename DIR>
00102 int get(char *msg, unsigned offset, unsigned limit)
00103 {
00104     typedef Svr_xmit<T> ct;
00105     int r = ct::to_svr(msg, offset, limit, this->v,
00106                       typename DIR::dir(), typename DIR::cls());
00107     if (L4_LIKELY(r >= 0))
00108         return Base::template get<DIR>(msg, r, limit);
00109
00110     if (_Elem<T>::Is_optional)
00111     {
00112         v = svr_type();
00113         return Base::template get<DIR>(msg, offset, limit);
00114     }
00115     return r;
00116 }
00117
00118 template<typename DIR>
00119 int set(char *msg, unsigned offset, unsigned limit, l4_ret_t ret)
00120 {
00121     typedef Svr_xmit<T> ct;
00122     int r = ct::from_svr(msg, offset, limit, ret, this->v,
00123                       typename DIR::dir(), typename DIR::cls());
00124     if (L4_UNLIKELY(r < 0))
00125         return r;
00126     return Base::template set<DIR>(msg, r, limit, ret);
00127 }
00128
00129 template<typename F, typename ...ARGS>
00130 decltype(auto) call(F f, ARGS ...args)
00131 {
00132     //As_arg<value_type> check;
00133     return Base::template
00134         call<F, ARGS..., svr_arg_type>(f, args..., this->v);
00135 }
00136
00137 template<typename O, typename FUNC, typename ...ARGS>
00138 decltype(auto) obj_call(O *o, ARGS ...args)
00139 {
00140     //As_arg<value_type> check;
00141     return Base::template
00142         obj_call<O, FUNC, ARGS..., svr_arg_type>(o, args..., this->v);
00143 }
00144 };
00145
00146 template<typename T, typename ...M>
00147 struct Svr_arg<T, void, M...> : Arg_pack<M...>
00148 {
00149     typedef Arg_pack<M...> Base;
00150
00151     template<typename DIR>
00152     int get(char *msg, unsigned offset, unsigned limit)
00153     { return Base::template get<DIR>(msg, offset, limit); }
00154
00155     template<typename DIR>
00156     int set(char *msg, unsigned offset, unsigned limit, l4_ret_t ret)
00157     { return Base::template set<DIR>(msg, offset, limit, ret); }
00158
00159     template<typename F, typename ...ARGS>
00160     decltype(auto) call(F f, ARGS ...args)
00161     {
00162         return Base::template call<F, ARGS...>(f, args...);
00163     }
00164
00165     template<typename O, typename FUNC, typename ...ARGS>
00166     decltype(auto) obj_call(O *o, ARGS ...args)
00167     {
00168         return Base::template obj_call<O, FUNC, ARGS...>(o, args...);
00169     }
00170 };
00171
00172 template<typename A, typename ...M>
00173 struct Arg_pack<A, M...> : Svr_arg<A, typename _Elem<A>::svr_type, M...>
00174 {};
00175
00176 } // namespace Detail
00177
00178 //-----
00183 template<typename IPC_TYPE> struct Svr_arg_pack;
00184
00185 template<typename R, typename ...ARGS>
00186 struct Svr_arg_pack<R (ARGS...)> : Detail::Arg_pack<ARGS...>

```

```

00187 {
00188     typedef Detail::Arg_pack<ARGS...> Base;
00189     template<typename DIR>
00190     int get(void *msg, unsigned offset, unsigned limit)
00191     {
00192         char *buf = static_cast<char *>(msg);
00193         return Base::template get<DIR>(buf, offset, limit);
00194     }
00195
00196     template<typename DIR>
00197     int set(void *msg, unsigned offset, unsigned limit, l4_ret_t ret)
00198     {
00199         char *buf = static_cast<char *>(msg);
00200         return Base::template set<DIR>(buf, offset, limit, ret);
00201     }
00202 };
00203
00207 template<typename IPC_TYPE, typename O, typename ...ARGS>
00208 static l4_msgtag_t
00209 handle_svr_obj_call(O *o, l4_utcb_t *utcb, l4_msgtag_t tag, ARGS ...args)
00210 {
00211     typedef Svr_arg_pack<typename IPC_TYPE::rpc::ipc_type> Pack;
00212     enum
00213     {
00214         Do_reply = IPC_TYPE::rpc::flags_type::Is_call,
00215         Short_err = Do_reply ? -L4_EMSTOOSHORT : -L4_ENOREPLY,
00216     };
00217
00218     // XXX: send a reply or just do not reply in case of a cheating client
00219     if (L4_UNLIKELY(tag.words() + tag.items() * Item_words > Mr_words))
00220         return l4_msgtag(Short_err, 0, 0, 0);
00221
00222     // our whole arguments data structure
00223     Pack pack;
00224     l4_msg_regs_t *mrs = l4_utcb_mr_u(utcb);
00225
00226     int in_pos = Detail::Sizeof<typename IPC_TYPE::opcode_type>::size;
00227
00228     unsigned const in_bytes = tag.words() * Word_bytes;
00229
00230     in_pos = pack.template get<Do_in_data>(&mrs->mr[0], in_pos, in_bytes);
00231
00232     if (L4_UNLIKELY(in_pos < 0))
00233         return l4_msgtag(Short_err, 0, 0, 0);
00234
00235     if (L4_UNLIKELY(pack.template get<Do_out_data>(mrs->mr, 0, Mr_bytes) < 0))
00236         return l4_msgtag(Short_err, 0, 0, 0);
00237
00238     in_pos = pack.template get<Do_in_items>(&mrs->mr[tag.words()], 0,
00239                                         tag.items() * Item_bytes);
00240
00241     if (L4_UNLIKELY(in_pos < 0))
00242         return l4_msgtag(Short_err, 0, 0, 0);
00243
00244     asm volatile (" : "=m" (mrs->mr));
00245
00246     // call the server function
00247     auto ret = pack.template obj_call<O, typename IPC_TYPE::rpc, ARGS...>(o, args...);
00248
00249     if (!Do_reply)
00250         return l4_msgtag(-L4_ENOREPLY, 0, 0, 0);
00251
00252     // our convention says that negative return value means no
00253     // reply data
00254     if (L4_UNLIKELY(ret < 0))
00255         return l4_msgtag(ret, 0, 0, 0);
00256
00257     // reply with the reply data from the server function
00258     int bytes = pack.template set<Do_out_data>(mrs->mr, 0, Mr_bytes, ret);
00259     if (L4_UNLIKELY(bytes < 0))
00260         return l4_msgtag(-L4_EMSTOOLONG, 0, 0, 0);
00261
00262     unsigned words = (bytes + Word_bytes - 1) / Word_bytes;
00263     bytes = pack.template set<Do_out_items>(&mrs->mr[words], 0,
00264                                         Mr_bytes - words * Word_bytes,
00265                                         ret);
00266     if (L4_UNLIKELY(bytes < 0))
00267         return l4_msgtag(-L4_EMSTOOLONG, 0, 0, 0);
00268
00269     unsigned const items = bytes / Item_bytes;
00270     return l4_msgtag(ret, words, items, 0);
00271 }
00272
00273 //-----
00274
00275
00276 template<typename RPCS, typename OPCODE_TYPE>

```

```

00277 struct Dispatch_call;
00278
00279 template<typename CLASS>
00280 struct Dispatch_call<L4::Typeid::Raw_ipc<CLASS>, void>
00281 {
00282     template<typename OBJ, typename ...ARGS>
00283     static l4_msgtag_t
00284     call(OBJ *o, l4_utcb_t *utcb, l4_msgtag_t tag, ARGS ...a)
00285     {
00286         return o->op_dispatch(utcb, tag, a...);
00287     }
00288 };
00289
00290 template<typename RPCS>
00291 struct Dispatch_call<RPCS, void>
00292 {
00293     constexpr static unsigned rmask()
00294     { return RPCS::rpc::flags_type::Rights & 3UL; }
00295
00296     template<typename OBJ, typename ...ARGS>
00297     static l4_msgtag_t
00298     call(OBJ *o, l4_utcb_t *utcb, l4_msgtag_t tag, unsigned rights, ARGS ...a)
00299     {
00300         if ((rights & rmask()) != rmask())
00301             return l4_msgtag(-L4_EPERM, 0, 0, 0);
00302
00303         typedef L4::Typeid::Rights<typename RPCS::rpc::class_type> Rights;
00304         return handle_svr_obj_call<RPCS>(o, utcb, tag,
00305                                         Rights(rights), a...);
00306     }
00307 };
00308
00309
00310 template<typename RPCS, typename OPCODE_TYPE>
00311 struct Dispatch_call
00312 {
00313     constexpr static unsigned rmask()
00314     { return RPCS::rpc::flags_type::Rights & 3UL; }
00315
00316     template<typename OBJ, typename ...ARGS>
00317     static l4_msgtag_t
00318     _call(OBJ *o, l4_utcb_t *utcb, l4_msgtag_t tag, unsigned rights, OPCODE_TYPE op, ARGS ...a)
00319     {
00320         if (L4::Types::Same<typename RPCS::opcode_type, void>::value
00321             || RPCS::Opcode == op)
00322         {
00323             if ((rights & rmask()) != rmask())
00324                 return l4_msgtag(-L4_EPERM, 0, 0, 0);
00325
00326             typedef L4::Typeid::Rights<typename RPCS::rpc::class_type> Rights;
00327             return handle_svr_obj_call<RPCS>(o, utcb, tag,
00328                                             Rights(rights), a...);
00329         }
00330         return Dispatch_call<typename RPCS::next, OPCODE_TYPE>::template
00331             _call<OBJ, ARGS...>(o, utcb, tag, rights, op, a...);
00332     }
00333
00334     template<typename OBJ, typename ...ARGS>
00335     static l4_msgtag_t
00336     call(OBJ *o, l4_utcb_t *utcb, l4_msgtag_t tag, unsigned rights, ARGS ...a)
00337     {
00338         OPCODE_TYPE op;
00339         unsigned limit = tag.words() * Word_bytes;
00340         typedef Svr_xmit<OPCODE_TYPE> S;
00341         l4_ret_t err = S::to_svr(reinterpret_cast<char *>(l4_utcb_mr_u(utcb)->mr), 0,
00342                                limit, op, Dir_in(), Cls_data());
00343         if (L4_UNLIKELY(err < 0))
00344             return l4_msgtag(-L4_MSGTOOSHORT, 0, 0, 0);
00345
00346         return _call<OBJ, ARGS...>(o, utcb, tag, rights, op, a...);
00347     }
00348 };
00349
00350 template<>
00351 struct Dispatch_call<Typeid::Detail::Rpc_end, void>
00352 {
00353     template<typename OBJ, typename ...ARGS>
00354     static l4_msgtag_t
00355     _call(OBJ *, l4_utcb_t *, l4_msgtag_t, unsigned, int, ARGS ...)
00356     { return l4_msgtag(-L4_ENOSYS, 0, 0, 0); }
00357
00358     template<typename OBJ, typename ...ARGS>
00359     static l4_msgtag_t
00360     call(OBJ *, l4_utcb_t *, l4_msgtag_t, unsigned, ARGS ...)
00361     { return l4_msgtag(-L4_ENOSYS, 0, 0, 0); }
00362 };
00363

```

```

00364 template<typename OPCODE_TYPE>
00365 struct Dispatch_call<Typeid::Detail::Rpc_end, OPCODE_TYPE> :
00366     Dispatch_call<Typeid::Detail::Rpc_end, void> {};
00367
00368 template<typename RPCS, typename OBJ, typename ...ARGS>
00369 static l4_msgtag_t
00370 dispatch_call(OBJ *o, l4_utcb_t *utcb, l4_msgtag_t tag, unsigned rights, ARGS ...a)
00371 {
00372     return Dispatch_call<typename RPCS::type, typename RPCS::opcode_type>::template
00373         call<OBJ, ARGS...>(o, utcb, tag, rights, a...);
00374 }
00375
00376 } // namespace Msg
00377 } // namespace Ipc
00378 } // namespace L4

```

## 16.481 ipc\_server\_loop

```

00001 // vi:set ft=c++: -- Mode: C++ --
00002 /*
00003  * Copyright (C) 2015, 2017, 2019, 2021-2025 Kernkonzept GmbH.
00004  * Author(s): Alexander Warg <alexander.warg@kernkonzept.com>
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00008 #pragma once
00009
00010 #include "ipc_epiface"
00011
00012 namespace L4 {
00013
00019     namespace Ipc_svr {
00020
00046         enum Reply_mode
00047         {
00048             Reply_compound,
00049             Reply_separate
00050         };
00051
00057         struct Ignore_errors
00058         { static void error(l4_msgtag_t, l4_utcb_t *) {} };
00059
00065         struct Default_timeout
00066         { static l4_timeout_t timeout() { return L4_IPC_SEND_TIMEOUT_0; } };
00067
00073         struct Compound_reply
00074         {
00075             static Reply_mode before_reply(l4_msgtag_t, l4_utcb_t *)
00076             { return Reply_compound; }
00077         };
00078
00084         struct Default_setup_wait
00085         { static void setup_wait(l4_utcb_t *, Reply_mode) {} };
00086
00094         template< typename R >
00095         struct Direct_dispatch
00096         {
00098             R &r;
00099
00101             Direct_dispatch(R &r) : r(r) {}
00102
00104             l4_msgtag_t operator () (l4_msgtag_t tag, l4_umword_t obj, l4_utcb_t *utcb)
00105             { return r.dispatch(tag, obj, utcb); }
00106         };
00107
00115         template< typename R >
00116         struct Direct_dispatch<R*>
00117         {
00119             R *r;
00120
00122             Direct_dispatch(R *r) : r(r) {}
00123
00125             l4_msgtag_t operator () (l4_msgtag_t tag, l4_umword_t obj, l4_utcb_t *utcb)
00126             { return r->dispatch(tag, obj, utcb); }
00127         };
00128
00129 #ifdef __EXCEPTIONS
00139         template< typename R, typename Exc> // = L4::Runtime_error>
00140         struct Exc_dispatch : private Direct_dispatch<R>
00141         {
00143             Exc_dispatch(R r) : Direct_dispatch<R>(r) {}
00144

```

```

00148 l4_msgtag_t operator () (l4_msgtag_t tag, l4_umword_t obj, l4_utcb_t *utcb)
00149 {
00150     try
00151     {
00152         return Direct_dispatch<R>::operator () (tag, obj, utcb);
00153     }
00154     catch (Exc &e)
00155     {
00156         return l4_msgtag(e.err_no(), 0, 0, 0);
00157     }
00158     catch (int err)
00159     {
00160         return l4_msgtag(err, 0, 0, 0);
00161     }
00162     catch (long err)
00163     {
00164         return l4_msgtag(err, 0, 0, 0);
00165     }
00166 }
00167 };
00168
00183 template< typename R, typename Exc, typename Printer >
00184 struct Dbg_dispatch : private Direct_dispatch<R>
00185 {
00187     Dbg_dispatch(R r, Printer p) : Direct_dispatch<R>(r), _printer(p) {}
00188
00193     l4_msgtag_t operator () (l4_msgtag_t tag, l4_umword_t obj, l4_utcb_t *utcb)
00194     {
00195         try
00196         {
00197             return Direct_dispatch<R>::operator () (tag, obj, utcb);
00198         }
00199         catch (Exc &e)
00200         {
00201             _printer.printf("Error in handling IPC: %s: %s\n", e.str(),
00202                             e.extra_str());
00203             return l4_msgtag(e.err_no(), 0, 0, 0);
00204         }
00205         catch (int err)
00206         {
00207             _printer.printf("Error in handling IPC: %d (%s)\n", err,
00208                             l4sys_errtostr(err));
00209             return l4_msgtag(err, 0, 0, 0);
00210         }
00211         catch (long err)
00212         {
00213             _printer.printf("Error in handling IPC: %ld (%s)\n", err,
00214                             l4sys_errtostr(err));
00215             return l4_msgtag(err, 0, 0, 0);
00216         }
00217     }
00218
00219     Printer _printer;
00220 };
00221 #endif
00222
00233 class Br_manager_no_buffers : public Server_iface
00234 {
00235 public:
00240     int alloc_buffer_demand(Demand const &demand) override
00241     {
00242         if (!demand.no_demand())
00243             return -L4_ENOMEM;
00244         return L4_EOK;
00245     }
00246
00248     L4::Cap<void> get_rcv_cap(int) const override
00249     { return L4::Cap<void>::Invalid; }
00250
00252     int realloc_rcv_cap(int) override
00253     { return -L4_ENOMEM; }
00254
00256     int add_timeout(Timeout *, l4_kernel_clock_t) override
00257     { return -L4_ENOSYS; }
00258
00260     int remove_timeout(Timeout *) override
00261     { return -L4_ENOSYS; }
00262
00263 protected:
00265     unsigned first_free_br() const
00266     { return 1; }
00267
00269     void setup_wait(l4_utcb_t *utcb, L4::Ipc_svr::Reply_mode)
00270     {
00271         l4_buf_regs_t *br = l4_utcb_br_u(utcb);
00272         br->bdr = 0;
00273         br->br[0] = 0;

```

```

00274     }
00275 };
00276
00285 struct Default_loop_hooks :
00286     public Ignore_errors, public Default_timeout, public Compound_reply,
00287     Br_manager_no_buffers
00288 {};
00289
00290 }
00291
00306 template< typename LOOP_HOOKS = Ipc_svr::Default_loop_hooks >
00307 class Server :
00308     public LOOP_HOOKS
00309 {
00310 public:
00317     /* Internal note: After all users have been converted, remove this
00318      * constructor. Also remove the constructor below then. */
00319     explicit Server(l4_utcb_t *)
00320         L4_DEPRECATED("Do not specify the UTCB with the constructor. "
00321             "Supply it on the loop function if needed.")
00322     {}
00323
00327     /* Internal note: Remove this constructor when the above deprecated
00328      * constructor with the UTCB pointer is also removed. */
00329     Server() {}
00330
00337     template< typename DISPATCH >
00338     inline L4_NORETURN void internal_loop(DISPATCH dispatch, l4_utcb_t *);
00339
00343     template< typename R >
00344     inline L4_NORETURN void loop_noexc(R r, l4_utcb_t *u = l4_utcb())
00345     { internal_loop(Ipc_svr::Direct_dispatch<R>(r), u); }
00346
00347 #ifdef __EXCEPTIONS
00354     template< typename EXC, typename R >
00355     inline L4_NORETURN void loop(R r, l4_utcb_t *u = l4_utcb())
00356     {
00357         internal_loop(Ipc_svr::Exc_dispatch<R, EXC>(r), u);
00358         // function will never return
00359     }
00360
00367     template< typename EXC, typename R, typename Printer >
00368     inline L4_NORETURN void loop_dbg(R r, Printer p, l4_utcb_t *u = l4_utcb())
00369     {
00370         internal_loop(Ipc_svr::Dbg_dispatch<R, EXC, Printer>(r, p), u);
00371         // function will never return
00372     }
00373 #endif
00374 protected:
00376     inline l4_msgtag_t reply_n_wait(l4_msgtag_t reply, l4_umword_t *p, l4_utcb_t *);
00377 };
00378
00379 template< typename L >
00380 inline l4_msgtag_t
00381 Server<L>::reply_n_wait(l4_msgtag_t reply, l4_umword_t *p, l4_utcb_t *utcb)
00382 {
00383     if (reply.label() != -L4_ENOREPLY)
00384     {
00385         Ipc_svr::Reply_mode m = this->before_reply(reply, utcb);
00386         if (m == Ipc_svr::Reply_compound)
00387         {
00388             this->setup_wait(utcb, m);
00389             return l4_ipc_reply_and_wait(utcb, reply, p, this->timeout());
00390         }
00391         else
00392         {
00393             l4_msgtag_t res = l4_ipc_send(L4_INVALID_CAP | L4_SYSF_REPLY, utcb, reply, this->timeout());
00394             if (res.has_error())
00395                 return res;
00396         }
00397     }
00398     this->setup_wait(utcb, Ipc_svr::Reply_separate);
00399     return l4_ipc_wait(utcb, p, this->timeout());
00400 }
00401
00402 template< typename L >
00403 template< typename DISPATCH >
00404 inline L4_NORETURN void
00405 Server<L>::internal_loop(DISPATCH dispatch, l4_utcb_t *utcb)
00406 {
00407     l4_msgtag_t res;
00408     l4_umword_t p;
00409     l4_msgtag_t r = l4_msgtag(-L4_ENOREPLY, 0, 0, 0);
00410
00411     while (true)
00412     {
00413         res = reply_n_wait(r, &p, utcb);

```

```

00414         if (res.has_error())
00415         {
00416             this->error(res, utcb);
00417             r = l4_msgtag(-L4_ENOREPLY, 0, 0, 0);
00418             continue;
00419         }
00420
00421         r = dispatch(res, p, utcb);
00422     }
00423 }
00424
00425 } // namespace L4

```

## 16.482 ipc\_string

```

00001 // vi:set ft=c++: -- Mode: C++ --
00002 /*
00003  * (c) 2014 Alexander Warg <alexander.warg@kernkonzept.com>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007 #pragma once
00008
00009 #include "types"
00010 #include "ipc_basics"
00011 #include "ipc_array"
00012
00013 namespace L4 { namespace Ipc {
00014
00015     template<typename CHAR = char const, typename LEN = unsigned long>
00016     struct String : Array<CHAR, LEN>
00017     {
00018         static LEN strlenlength(CHAR *d) { LEN l = 0; while (d[l]) ++l; return l; }
00019         String() {}
00020         String(CHAR *d) : Array<CHAR, LEN>(strlenlength(d) + 1, d) {}
00021         String(LEN len, CHAR *d) : Array<CHAR, LEN>(len, d) {}
00022         void copy_in(CHAR const *s)
00023         {
00024             if (this->length < 1)
00025                 return;
00026
00027             LEN i;
00028             for (i = 0; i < this->length - 1 && s[i]; ++i)
00029                 this->data[i] = s[i];
00030             this->length = i + 1;
00031             this->data[i] = CHAR();
00032         }
00033     };
00034
00035     #if __cplusplus >= 201103L
00036     template< typename CHAR = char, typename LEN_TYPE = unsigned long,
00037             LEN_TYPE MAX = (L4_UTCB_GENERIC_DATA_SIZE *
00038                 sizeof(l4_umword_t)) / sizeof(CHAR) >
00039     using String_in_buf = Array_in_buf<CHAR, LEN_TYPE, MAX>;
00040     #endif
00041
00042     namespace Msg {
00043     template<typename A, typename LEN>
00044     struct Clnt_xmit< String<A, LEN> > : Clnt_xmit< Array<A, LEN> > {};
00045
00046     template<typename A, typename LEN, typename CLASS>
00047     struct Svr_val_ops< String<A, LEN>, Dir_in, CLASS >
00048     : Svr_val_ops< Array_ref<A, LEN>, Dir_in, CLASS >
00049     {
00050         typedef Svr_val_ops< Array_ref<A, LEN>, Dir_in, CLASS > Base;
00051         typedef typename Base::svr_type svr_type;
00052         using Base::to_svr;
00053         static int to_svr(char *msg, unsigned offset, unsigned limit,
00054             svr_type &a, Dir_in dir, Cls_data cls)
00055         {
00056             int r = Base::to_svr(msg, offset, limit, a, dir, cls);
00057             if (r < 0)
00058                 return r;
00059
00060             // correct clients send at least the zero terminator
00061             if (a.length < 1)
00062                 return -L4_EMSTOOSHORT;
00063
00064             typedef typename L4::Types::Remove_const<A>::type elem_type;
00065             const_cast<elem_type*>(a.data)[a.length - 1] = A();
00066             return r;
00067         }
00068     };

```



```

00069
00070 template<typename A, typename LEN>
00071 struct Clnt_xmit<String<A, LEN> &> : Clnt_xmit<Array<A, LEN> &>
00072 {
00073     typedef Array<A, LEN> &type;
00074
00075     using Clnt_xmit<type>::from_msg;
00076     static int from_msg(char *msg, unsigned offset, unsigned limit, long ret,
00077                         Array<A, LEN> &a, Dir_out dir, Cls_data cls)
00078     {
00079         int r = Clnt_xmit<type>::from_msg(msg, offset, limit, ret, a, dir, cls);
00080         if (r < 0)
00081             return r;
00082
00083         // check for a bad servers
00084         if (a.length < 1)
00085             return -L4_MSGTOOSHORT;
00086
00087         a.data[a.length - 1] = A();
00088         return r;
00089     };
00090 };
00091
00092 template<typename A, typename LEN>
00093 struct Clnt_xmit<String<A, LEN> *> : Clnt_xmit<String<A, LEN> &> {};
00094
00095 template<typename A, typename LEN, typename CLASS>
00096 struct Svr_val_ops<String<A, LEN>, Dir_out, CLASS>
00097 : Svr_val_ops<Array_ref<A, LEN>, Dir_out, CLASS>
00098 {};
00099
00100 template<typename A, typename LEN>
00101 struct Is_valid_rpc_type<String<A, LEN> const *> : L4::Types::False {};
00102 template<typename A, typename LEN>
00103 struct Is_valid_rpc_type<String<A, LEN> const &> : L4::Types::False {};
00104
00105 } // namespace Msg
00106
00107 }

```


## 16.483 l4/sys/cxx/ipc\_types File Reference

```


#include "capability.h"
#include "types"
#include "ipc_basics"

```

Include dependency graph for ipc\_types:



This graph shows which files directly or indirectly include this file:



## Data Structures

- struct [L4::lpc::In\\_out< T >](#)  
Mark an argument as in-out argument.
- struct [L4::lpc::As\\_value< T >](#)  
Pass the argument as plain data value.
- struct [L4::lpc::Opt< T >](#)  
Attribute for defining an optional RPC argument.
- class [L4::lpc::Small\\_buf](#)  
A receive item for receiving a single object capability.
- class [L4::lpc::Gen\\_fpage](#)  
Generic RPC base for typed message items.
- class [L4::lpc::Snd\\_fpage](#)  
Send item or return item.
- class [L4::lpc::Rcv\\_fpage](#)  
Non-small receive item.
- class [L4::lpc::Cap< T >](#)  
Capability type for RPC interfaces (see [L4::Cap< T>](#)).

## Namespaces

- namespace `L4`  
*L4 low-level kernel interface.*
- namespace `L4::lpc`  
*IPC related functionality.*
- namespace `L4::lpc::Msg`  
*IPC Message related functionality.*

## Functions

- `template<typename T>`  
`Cap< T > L4::lpc::make_cap (L4::Cap< T > cap, unsigned rights) noexcept`  
*Make an `L4::lpc::Cap< T >` for the given capability and rights.*
- `template<typename T>`  
`Cap< T > L4::lpc::make_cap_rw (L4::Cap< T > cap) noexcept`  
*Make an `L4::lpc::Cap< T >` for the given capability with `L4_CAP_FPAGE_RW` rights.*
- `template<typename T>`  
`Cap< T > L4::lpc::make_cap_rws (L4::Cap< T > cap) noexcept`  
*Make an `L4::lpc::Cap< T >` for the given capability with `L4_CAP_FPAGE_RWS` rights.*
- `template<typename T>`  
`Cap< T > L4::lpc::make_cap_full (L4::Cap< T > cap) noexcept`  
*Make an `L4::lpc::Cap< T >` for the given capability with full fpage and object-specific rights.*

## 16.484 ipc\_types

[Go to the documentation of this file.](#)

```
00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00002 /*
00003  * (c) 2014 Alexander Warg <alexander.warg@kernkonzept.com>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007 #pragma once
00008
00009 #include "capability.h"
00010 #include "types"
00011 #include "ipc_basics"
00012
00013 namespace L4 {
00014
00015     typedef int Opcode;
00016
00017     namespace Ipc {
00018
00019         template<typename T> struct L4_EXPORT Out;
00020
00021         template<typename T> struct L4_EXPORT In_out
00022         {
00023             T v;
00024             In_out() {}
00025             In_out(T v) : v(v) {}
00026             operator T () const { return v; }
00027             operator T & () { return v; }
00028         };
00029
00030         namespace Msg {
00031             template<typename A> struct Elem< In_out<A> > : Elem<A> {};
00032
00033             template<typename A>
00034             struct Svr_xmit< In_out<A> > : Svr_xmit<A>, Svr_xmit<A const> *
00035             {
00036                 using Svr_xmit<A>::from_svr;
00037                 using Svr_xmit<A const>::to_svr;
00038             };
00039         }
00040     }
00041 }
```

```

00058 };
00059
00060 template<typename A>
00061 struct Clnt_xmit< In_out<A *> > : Clnt_xmit<A *>, Clnt_xmit<A const *>
00062 {
00063     using Clnt_xmit<A *>::from_msg;
00064     using Clnt_xmit<A const *>::to_msg;
00065 };
00066
00067 template<typename A>
00068 struct Is_valid_rpc_type< In_out<A *> > : Is_valid_rpc_type<A *> {};
00069 template<typename A>
00070 struct Is_valid_rpc_type< In_out<A const *> > : L4::Types::False {};
00071
00072 #ifdef CONFIG_ALLOW_REFS
00073 template<typename A> struct Elem< In_out<A &> > : Elem<A &> {};
00074
00075 template<typename A>
00076 struct Svr_xmit< In_out<A &> > : Svr_xmit<A &>, Svr_xmit<A const &>
00077 {
00078     using Svr_xmit<A &>::from_svr;
00079     using Svr_xmit<A const &>::to_svr;
00080 };
00081
00082 template<typename A>
00083 struct Clnt_xmit< In_out<A &> > : Clnt_xmit<A &>, Clnt_xmit<A const &>
00084 {
00085     using Clnt_xmit<A &>::from_msg;
00086     using Clnt_xmit<A const &>::to_msg;
00087 };
00088
00089 template<typename A>
00090 struct Is_valid_rpc_type< In_out<A &> > : Is_valid_rpc_type<A &> {};
00091 template<typename A>
00092 struct Is_valid_rpc_type< In_out<A const &> > : L4::Types::False {};
00093
00094 #else
00095
00096 template<typename A>
00097 struct Is_valid_rpc_type< In_out<A &> > : L4::Types::False {};
00098
00099 #endif
00100
00101 // Value types don't make sense for output.
00102 template<typename A>
00103 struct Is_valid_rpc_type< In_out<A> > : L4::Types::False {};
00104
00105 }
00106
00107
00116 template<typename T> struct L4_EXPORT As_value
00117 {
00118     typedef T value_type;
00119     T v;
00120     As_value() noexcept {}
00121     As_value(T v) noexcept : v(v) {}
00122     operator T () const noexcept { return v; }
00123     operator T & () noexcept { return v; }
00124 };
00125
00126 namespace Msg {
00127 template<typename T> struct Class< As_value<T> > : Cls_data {};
00128 template<typename T> struct Elem< As_value<T> > : Elem<T> {};
00129 template<typename T> struct Elem< As_value<T> *> : Elem<T *> {};
00130 }
00131
00132
00136 template<typename T> struct L4_EXPORT Opt
00137 {
00138     T _value;
00139     bool _valid;
00140
00142     Opt() noexcept : _valid(false) {}
00143
00145     Opt(T value) noexcept : _value(value), _valid(true) {}
00146
00148     Opt &operator = (T value) noexcept
00149     {
00150         this->_value = value;
00151         this->_valid = true;
00152         return *this;
00153     }
00154
00156     void set_valid(bool valid = true) noexcept { _valid = valid; }
00157
00159     T *operator -> () noexcept { return &this->_value; }
00161     T const *operator -> () const noexcept { return &this->_value; }

```

```

00163     T value() const noexcept { return this->_value; }
00165     T &value() noexcept { return this->_value; }
00167     bool is_valid() const noexcept { return this->_valid; }
00168 };
00169
00170 namespace Msg {
00171 template<typename T> struct Elem< Opt<T &> > : Elem<T &>
00172 {
00173     enum { Is_optional = true };
00174     typedef Opt<typename Elem<T &>::svr_type> &svr_arg_type;
00175     typedef Opt<typename Elem<T &>::svr_type> svr_type;
00176 };
00177
00178 template<typename T> struct Elem< Opt<T *> > : Elem<T *>
00179 {
00180     enum { Is_optional = true };
00181     typedef Opt<typename Elem<T *>::svr_type> &svr_arg_type;
00182     typedef Opt<typename Elem<T *>::svr_type> svr_type;
00183 };
00184
00185
00186
00187 template<typename T, typename CLASS>
00188 struct Svr_val_ops<Opt<T>, Dir_out, CLASS> : Svr_noops< Opt<T> >
00189 {
00190     typedef Opt<T> svr_type;
00191     typedef Svr_val_ops<T, Dir_out, CLASS> Native;
00192
00193     using Svr_noops< Opt<T> >::to_svr;
00194     static int to_svr(char *msg, unsigned offset, unsigned limit,
00195                     Opt<T> &arg, Dir_out, CLASS) noexcept
00196     {
00197         return Native::to_svr(msg, offset, limit, arg.value(), Dir_out(), CLASS());
00198     }
00199
00200     using Svr_noops< Opt<T> >::from_svr;
00201     static int from_svr(char *msg, unsigned offset, unsigned limit, l4_ret_t ret,
00202                     svr_type &arg, Dir_out, CLASS) noexcept
00203     {
00204         if (arg.is_valid())
00205             return Native::from_svr(msg, offset, limit, ret, arg.value(),
00206                                     Dir_out(), CLASS());
00207         return offset;
00208     }
00209 };
00210
00211 template<typename T> struct Elem< Opt<T> > : Elem<T>
00212 {
00213     enum { Is_optional = true };
00214     typedef Opt<T> arg_type;
00215 };
00216
00217 template<typename T> struct Elem< Opt<T const *> > : Elem<T const *>
00218 {
00219     enum { Is_optional = true };
00220     typedef Opt<T const *> arg_type;
00221 };
00222
00223 template<typename T>
00224 struct Is_valid_rpc_type< Opt<T const &> > : L4::Types::False {};
00225
00226 template<typename T, typename CLASS>
00227 struct Clnt_val_ops<Opt<T>, Dir_in, CLASS> : Clnt_noops< Opt<T> >
00228 {
00229     typedef Opt<T> arg_type;
00230     typedef Detail::_Clnt_val_ops<typename Elem<T>::arg_type, Dir_in, CLASS> Native;
00231
00232     using Clnt_noops< Opt<T> >::to_msg;
00233     static int to_msg(char *msg, unsigned offset, unsigned limit,
00234                     arg_type arg, Dir_in, CLASS) noexcept
00235     {
00236         if (arg.is_valid())
00237             return Native::to_msg(msg, offset, limit,
00238                                   Detail::_Plain<T>::deref(arg.value()),
00239                                   Dir_in(), CLASS());
00240         return offset;
00241     }
00242 };
00243
00244 template<typename T> struct Class< Opt<T> > :
00245     Class< typename Detail::_Plain<T>::type > {};
00246 template<typename T> struct Direction< Opt<T> > : Direction<T> {};
00247 }
00248
00257 class L4_EXPORT Small_buf
00258 {
00259 public:

```

```

00267     explicit Small_buf(L4::Cap<void> cap, unsigned long flags = 0) noexcept
00268     : _data(cap.cap() | L4_RCV_ITEM_SINGLE_CAP | flags) {}
00269
00274     explicit Small_buf(l4_cap_idx_t cap, unsigned long flags = 0) noexcept
00275     : _data(cap | L4_RCV_ITEM_SINGLE_CAP | flags) {}
00276
00278     l4_umword_t raw() const noexcept { return _data; }
00279 private:
00280     l4_umword_t _data;
00281 };
00282
00286 class L4_EXPORT Gen_fpage
00287 {
00288 public:
00290     enum Type
00291     {
00292         Special = L4_FPAGE_SPECIAL « 4,
00293         Memory  = L4_FPAGE_MEMORY   « 4,
00294         Io       = L4_FPAGE_IO       « 4,
00295         Obj      = L4_FPAGE_OBJ      « 4
00296     };
00297
00299     Gen_fpage(l4_umword_t base, l4_umword_t data) noexcept
00300     : _base(base), _data(data)
00301     {}
00302
00304     l4_umword_t data() const noexcept { return _data; }
00306     l4_umword_t base_x() const noexcept { return _base; }
00307
00308 protected:
00309     l4_umword_t _base;
00310     l4_umword_t _data;
00311 };
00312
00323 class Snd_fpage : public Gen_fpage
00324 {
00325 public:
00328     enum Map_type
00329     {
00330         Map    = L4_MAP_ITEM_MAP,
00331         Grant  = L4_MAP_ITEM_GRANT,
00332     };
00333
00336     enum Cacheopt
00337     {
00338         None    = 0,
00339         Cached  = L4_FPAGE_CACHEABLE « 4,
00340         Buffered = L4_FPAGE_BUFFERABLE « 4,
00341         Uncached = L4_FPAGE_UNCACHEABLE « 4
00342     };
00343
00346     enum Continue
00347     {
00348         Single  = 0,
00349         Last    = 0,
00350         More    = L4_ITEM_CONT,
00351         Compound = L4_ITEM_CONT,
00352     };
00353
00355     Snd_fpage(l4_umword_t base = 0, l4_umword_t data = 0) noexcept
00356     : Gen_fpage(base, data)
00357     {}
00358
00370     Snd_fpage(l4_fpage_t const &fp, l4_addr_t snd_base = 0,
00371               Map_type map_type = Map,
00372               Cacheopt cache = None, Continue cont = Last) noexcept
00373     : Gen_fpage(L4_ITEM_MAP | (snd_base & (~0UL « 12)) | l4_umword_t(map_type)
00374               | l4_umword_t(cache) | l4_umword_t(cont),
00375               fp.raw())
00376     {}
00377
00386     Snd_fpage(L4::Cap<void> cap, unsigned rights, Map_type map_type = Map) noexcept
00387     : Gen_fpage(L4_ITEM_MAP | l4_umword_t(map_type) | (rights & 0xf0),
00388               cap.fpage(rights).raw())
00389     {}
00390
00402     static Snd_fpage obj(l4_cap_idx_t base, int order,
00403                         unsigned char rights,
00404                         l4_addr_t snd_base = 0,
00405                         Map_type map_type = Map,
00406                         Continue cont = Last) noexcept
00407     {
00408         return Snd_fpage(l4_obj_fpage(base, order, rights), snd_base,
00409                         map_type, None, cont);
00410     }
00411
00424     static Snd_fpage mem(l4_addr_t base, int order,

```

```

00425         unsigned char rights,
00426         l4_addr_t snd_base = 0,
00427         Map_type map_type = Map,
00428         Cacheopt cache = None, Continue cont = Last) noexcept
00429     {
00430         return Snd_fpage(l4_fpage(base, order, rights), snd_base, map_type, cache,
00431             cont);
00432     }
00433
00445 static Snd_fpage io(unsigned long base, int order,
00446     unsigned char rights,
00447     l4_addr_t snd_base = 0,
00448     Map_type map_type = Map,
00449     Continue cont = Last) noexcept
00450 {
00451     return Snd_fpage(l4_fpage_set_rights(l4_iofpage(base, order), rights),
00452         snd_base, map_type, None, cont);
00453 }
00454
00457 unsigned order() const noexcept { return (_data >> 6) & 0x3f; }
00458
00461 unsigned snd_order() const noexcept { return (_data >> 6) & 0x3f; }
00462
00465 unsigned rcv_order() const noexcept { return (_base >> 6) & 0x3f; }
00466
00469 l4_addr_t base() const noexcept { return _data & (~0UL << 12); }
00470
00473 l4_addr_t snd_base() const noexcept { return _base & (~0UL << 12); }
00474
00477 void snd_base(l4_addr_t b) noexcept { _base = (_base & ~(~0UL << 12)) | (b & (~0UL << 12)); }
00478
00480 bool is_valid() const noexcept { return _base & L4_ITEM_MAP; }
00481
00496 bool cap_received() const noexcept { return (_base & 0x3e) == 0x38; }
00512 bool id_received() const noexcept { return (_base & 0x3e) == 0x3c; }
00528 bool local_id_received() const noexcept { return (_base & 0x3e) == 0x3e; }
00535 bool is_compound() const noexcept { return _base & 1; }
00536 };
00537
00544 class Rcv_fpage : public Gen_fpage
00545 {
00546 public:
00550 Rcv_fpage() noexcept : Gen_fpage(0, 0), _rcv_task(L4_INVALID_CAP) {}
00551
00561 Rcv_fpage(l4_fpage_t const &fp, l4_addr_t snd_base = 0,
00562     l4_cap_idx_t rcv_task = L4_INVALID_CAP) noexcept
00563 : Gen_fpage(L4_ITEM_MAP | (snd_base & (~0UL << 12))
00564     | (l4_is_valid_cap(rcv_task) ? L4_RCV_ITEM_FORWARD_MAPPINGS : 0),
00565     fp.raw),
00566     _rcv_task(rcv_task)
00567 {}
00568
00578 static Rcv_fpage obj(l4_cap_idx_t base, int order, l4_addr_t snd_base = 0,
00579     L4::Cap<void> rcv_task = L4::Cap<void>::Invalid) noexcept
00580 {
00581     return Rcv_fpage(l4_obj_fpage(base, order, 0), snd_base,
00582         rcv_task.cap());
00583 }
00584
00594 static Rcv_fpage mem(l4_addr_t base, int order, l4_addr_t snd_base = 0,
00595     L4::Cap<void> rcv_task = L4::Cap<void>::Invalid) noexcept
00596 {
00597     return Rcv_fpage(l4_fpage(base, order, 0), snd_base, rcv_task.cap());
00598 }
00599
00609 static Rcv_fpage io(unsigned long base, int order, l4_addr_t snd_base = 0,
00610     L4::Cap<void> rcv_task = L4::Cap<void>::Invalid) noexcept
00611 {
00612     return Rcv_fpage(l4_iofpage(base, order), snd_base, rcv_task.cap());
00613 }
00614
00620 l4_cap_idx_t rcv_task() const { return _rcv_task; }
00621
00625 bool forward_mappings() const noexcept
00626 { return _base & L4_RCV_ITEM_FORWARD_MAPPINGS; }
00627
00628 protected:
00629     l4_cap_idx_t _rcv_task;
00630 };
00631
00632 namespace Msg {
00633
00634 // Snd_fpage are out items
00636 template<> struct Class<L4::Ipc::Snd_fpage> : Cls_item {};
00637
00638 // Rcv_fpage are buffer items

```

```

00639 template<> struct Class<L4::Rpc::Rcv_fpage> : Cls_buffer {};
00640
00641 template<>
00642 struct Clnt_val_ops<L4::Rpc::Rcv_fpage, Dir_in, Cls_buffer>
00643 : Clnt_noops<L4::Rpc::Rcv_fpage>
00644 {
00645     using Clnt_noops<L4::Rpc::Rcv_fpage>::to_msg;
00646
00647     static int to_msg(char *msg, unsigned offs, unsigned limit,
00648                     L4::Rpc::Rcv_fpage arg, Dir_in, Cls_buffer) noexcept
00649     {
00650         offs = align_to<l4_umword_t>(offs);
00651         unsigned words = arg.forward_mappings() ? 3 : 2;
00652         if (L4_UNLIKELY(!check_size<l4_umword_t>(offs, limit, words)))
00653             return -L4_EMSGTOOLONG;
00654         auto *buf = reinterpret_cast<l4_umword_t*>(msg + offs);
00655         *buf++ = arg.base_x();
00656         *buf++ = arg.data();
00657         if (arg.forward_mappings())
00658             *buf++ = arg.rcv_task();
00659         return offs + sizeof(l4_umword_t) * words;
00660     }
00661 };
00662
00663
00664 // Remove receive buffers from server-side arguments
00665 template<> struct Elem<L4::Rpc::Rcv_fpage>
00666 {
00667     typedef L4::Rpc::Rcv_fpage arg_type;
00668     typedef void svr_type;
00669     typedef void svr_arg_type;
00670     enum { Is_optional = false };
00671 };
00672
00673 // Small_buf are buffer items
00674 template<> struct Class<L4::Rpc::Small_buf> : Cls_buffer {};
00675
00676 // Remove receive buffers from server-side arguments
00677 template<> struct Elem<L4::Rpc::Small_buf>
00678 {
00679     typedef L4::Rpc::Small_buf arg_type;
00680     typedef void svr_type;
00681     typedef void svr_arg_type;
00682     enum { Is_optional = false };
00683 };
00684 } // namespace Msg
00685
00686 // L4::Cap<> handling
00687
00698 template<typename T> class Cap
00699 {
00700     template<typename O> friend class Cap;
00701     l4_umword_t _cap_n_rights;
00702
00703 public:
00704     enum
00705     {
00711         Rights_mask = 0xff,
00712
00717         Cap_mask    = L4_CAP_MASK
00718     };
00719
00720     template<typename O>
00722     Cap(Cap<O> const &o) noexcept : _cap_n_rights(o._cap_n_rights)
00723     {
00724         L4::Cap<T>::template check_convertible_from<O>();
00725     }
00726
00728     Cap(L4::Cap<T> cap) noexcept
00729     : _cap_n_rights((cap.cap() & Cap_mask) | (cap ? L4_CAP_FPAGE_R : 0))
00730     {}
00731
00733     template<typename O>
00734     Cap(L4::Cap<O> cap) noexcept
00735     : _cap_n_rights((cap.cap() & Cap_mask) | (cap ? L4_CAP_FPAGE_R : 0))
00736     {
00737         L4::Cap<T>::template check_convertible_from<O>();
00738     }
00739
00741     Cap() noexcept : _cap_n_rights(L4_INVALID_CAP) {}
00742
00750     Cap(L4::Cap<T> cap, unsigned char rights) noexcept
00751     : _cap_n_rights((cap.cap() & Cap_mask) | (rights & Rights_mask)) {}
00752
00758     static Cap from_ci(l4_cap_idx_t c) noexcept
00759     { return Cap(L4::Cap<T>(c & Cap_mask), c & Rights_mask); }
00760

```



```

00762 L4::Cap<T> cap() const noexcept
00763 { return L4::Cap<T>(_cap_n_rights & Cap_mask); }
00764
00766 unsigned rights() const noexcept
00767 { return _cap_n_rights & Rights_mask; }
00768
00770 L4::Ipc::Snd_fpage fpage() const noexcept
00771 { return L4::Ipc::Snd_fpage(cap(), rights()); }
00772
00774 bool is_valid() const noexcept
00775 { return !(_cap_n_rights & L4_INVALID_CAP_BIT); }
00776 };
00777
00784 template<typename T>
00785 Cap<T> make_cap(L4::Cap<T> cap, unsigned rights) noexcept
00786 { return Cap<T>(cap, rights); }
00787
00794 template<typename T>
00795 Cap<T> make_cap_rw(L4::Cap<T> cap) noexcept
00796 { return Cap<T>(cap, L4_CAP_FPAGE_RW); }
00797
00804 template<typename T>
00805 Cap<T> make_cap_rws(L4::Cap<T> cap) noexcept
00806 { return Cap<T>(cap, L4_CAP_FPAGE_RWS); }
00807
00823 template<typename T>
00824 Cap<T> make_cap_full(L4::Cap<T> cap) noexcept
00825 { return Cap<T>(cap, L4_CAP_FPAGE_RWS | L4_FPAGE_C_OBJ_RIGHTS); }
00826
00827 // caps are special the have an invalid representation
00828 template<typename T> struct L4_EXPORT Opt< Cap<T> >
00829 {
00830     Cap<T> _value;
00831     Opt() noexcept {}
00832     Opt(Cap<T> value) noexcept : _value(value) {}
00833     Opt(L4::Cap<T> value) noexcept : _value(value) {}
00834     Opt &operator = (Cap<T> value) noexcept
00835     { this->_value = value; return *this; }
00836     Opt &operator = (L4::Cap<T> value) noexcept
00837     { this->_value = value; return *this; }
00838
00839     Cap<T> value() const noexcept { return this->_value; }
00840     bool is_valid() const noexcept { return this->_value.is_valid(); }
00841 };
00842
00843
00844 namespace Msg {
00845     // prohibit L4::Cap as argument
00846     template<typename A>
00847     struct Is_valid_rpc_type< L4::Cap<A> > : L4::Types::False {};
00848
00849     template<typename A> struct Class< Cap<A> > : Cls_item {};
00850     template<typename A> struct Elem< Cap<A> >
00851     {
00852         enum { Is_optional = false };
00853         typedef Cap<A> arg_type;
00854         typedef L4::Ipc::Snd_fpage svr_type;
00855         typedef L4::Ipc::Snd_fpage svr_arg_type;
00856     };
00857
00858
00859     template<typename A, typename CLASS>
00860     struct Svr_val_ops<Cap<A>, Dir_in, CLASS> :
00861         Svr_val_ops<L4::Ipc::Snd_fpage, Dir_in, CLASS>
00862     {};
00863
00864     template<typename A, typename CLASS>
00865     struct Clnt_val_ops<Cap<A>, Dir_in, CLASS> :
00866         Clnt_noops< Cap<A> >
00867     {
00868         using Clnt_noops< Cap<A> >::to_msg;
00869
00870         static int to_msg(char *msg, unsigned offset, unsigned limit,
00871             Cap<A> arg, Dir_in, Cls_item) noexcept
00872         {
00873             // passing an invalid cap as mandatory argument is an error
00874             // XXX: This checks for a client calling error, we could
00875             //      also just ignore this for performance reasons and
00876             //      let the client fail badly (Alex: I'd prefer this)
00877             if (L4_UNLIKELY(!arg.is_valid()))
00878                 return -L4_EMSGMISSARG;
00879
00880             return msg_add(msg, offset, limit, arg.fpage());
00881         }
00882     };
00883
00884     template<typename A>

```

```

00885 struct Elem<Out<L4::Cap<A> > >
00886 {
00887     enum { Is_optional = false };
00888     typedef L4::Cap<A> arg_type;
00889     typedef Ipc::Cap<A> svr_type;
00890     typedef svr_type &svr_arg_type;
00891 };
00892
00893 template<typename A> struct Direction< Out< L4::Cap<A> > > : Dir_out {};
00894 template<typename A> struct Class< Out< L4::Cap<A> > > : Cls_item {};
00895
00896 template<typename A>
00897 struct Clnt_val_ops< L4::Cap<A>, Dir_out, Cls_item > :
00898     Clnt_noops< L4::Cap<A> >
00899 {
00900     using Clnt_noops< L4::Cap<A> >::to_msg;
00901     static int to_msg(char *msg, unsigned offset, unsigned limit,
00902                     L4::Cap<A> arg, Dir_in, Cls_buffer) noexcept
00903     {
00904         if (L4_UNLIKELY(!arg.is_valid()))
00905             return -L4_MSGMISSARG; // no buffer inserted
00906         return msg_add(msg, offset, limit, Small_buf(arg));
00907     }
00908 };
00909
00910 template<typename A>
00911 struct Svr_val_ops< L4::Ipc::Cap<A>, Dir_out, Cls_item > :
00912     Svr_noops<Cap<A> &>
00913 {
00914     using Svr_noops<Cap<A> &>::from_svr;
00915     static int from_svr(char *msg, unsigned offset, unsigned limit, long,
00916                       Cap<A> arg, Dir_out, Cls_item) noexcept
00917     {
00918         if (L4_UNLIKELY(!arg.is_valid()))
00919             // do not map anything
00920             return msg_add(msg, offset, limit, L4::Ipc::Snd_fpage(arg.cap(), 0));
00921         return msg_add(msg, offset, limit, arg.fpage());
00922     }
00923 };
00924 };
00925
00926 // prohibit a UTCB pointer as normal RPC argument
00927 template<> struct Is_valid_rpc_type<l4_utcb_t *> : L4::Types::False {};
00928
00929 } // namespace Msg
00930 } // namespace Ipc
00931 } // namespace L4

```

## 16.485 ipc\_varg

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00002 /*
00003  * (c) 2014 Alexander Warg <alexander.warg@kernkonzept.com>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007 #pragma once
00008 #pragma GCC system_header
00009
00010 #include "types"
00011 #include "ipc_basics"
00012
00013 namespace L4 { namespace Ipc L4_EXPORT {
00014
00015     template< typename T, template <typename X> class B >
00016     struct Generic_va_type : B<T>
00017     {
00018         enum { Id = B<T>::Id };
00019         typedef B<T> ID;
00020         typedef T const &Ret_value;
00021         typedef T Value;
00022
00023         static Ret_value value(void const *d)
00024         { return *reinterpret_cast<Value const *>(d); }
00025
00026         static void const *addr_of(Value const &v) { return &v; }
00027
00028         static unsigned size(void const *) { return sizeof(T); }
00029
00030         static L4_varg_type unsigned_id()
00031         {
00032             return static_cast<L4_varg_type>(Id & ~L4_VARG_TYPE_SIGN);
00033         }
00034     };

```

```

00034
00035     static L4_varg_type signed_id()
00036     {
00037         return static_cast<L4_varg_type>(Id | L4_VARG_TYPE_SIGN);
00038     }
00039
00040     static L4_varg_type id()
00041     {
00042         return static_cast<L4_varg_type>(Id);
00043     }
00044 };
00045
00046 template< typename T > struct Va_type_id;
00047 template<> struct Va_type_id<l4_umword_t> { enum { Id = L4_VARG_TYPE_UMWORD }; };
00048 template<> struct Va_type_id<l4_mword_t> { enum { Id = L4_VARG_TYPE_MWORD }; };
00049 template<> struct Va_type_id<l4_fpage_t> { enum { Id = L4_VARG_TYPE_FPAGE }; };
00050 template<> struct Va_type_id<void> { enum { Id = L4_VARG_TYPE_NIL }; };
00051 template<> struct Va_type_id<char const *> { enum { Id = L4_VARG_TYPE_STRING }; };
00052
00053 template< typename T > struct Va_type;
00054
00055 template<> struct Va_type<l4_umword_t> : Generic_va_type<l4_umword_t, Va_type_id> {};
00056 template<> struct Va_type<l4_mword_t> : Generic_va_type<l4_mword_t, Va_type_id> {};
00057 template<> struct Va_type<l4_fpage_t> : Generic_va_type<l4_fpage_t, Va_type_id> {};
00058
00059 template<> struct Va_type<void>
00060 {
00061     typedef void Ret_value;
00062     typedef void Value;
00063
00064     static void const *addr_of(void) { return 0; }
00065
00066     static void value(void const *) {}
00067     static L4_varg_type id() { return L4_VARG_TYPE_NIL; }
00068     static unsigned size(void const *) { return 0; }
00069 };
00070
00071 template<> struct Va_type<char const *>
00072 {
00073     typedef char const *Ret_value;
00074     typedef char const *Value;
00075
00076     static void const *addr_of(Value v) { return v; }
00077
00078     static L4_varg_type id() { return L4_VARG_TYPE_STRING; }
00079     static unsigned size(void const *s)
00080     {
00081         char const *_s = reinterpret_cast<char const *>(s);
00082         int l = 1;
00083         while (*_s)
00084         {
00085             ++_s; ++l;
00086         }
00087         return l;
00088     }
00089
00090     static Ret_value value(void const *d) { return static_cast<char const *>(d); }
00091 };
00092
00096 class Varg
00097 {
00098 private:
00099     enum { Direct_data = 0x8000 };
00100     l4_umword_t _tag;
00101     char const *_d;
00102
00103 public:
00104
00106     typedef l4_umword_t Tag;
00107
00109     L4_varg_type type() const { return static_cast<L4_varg_type>(_tag & 0xff); }
00114     unsigned length() const { return _tag >> 16; }
00116     Tag tag() const { return _tag & ~Direct_data; }
00118     void tag(Tag tag) { _tag = tag; }
00120     void data(char const *d) { _d = d; }
00121
00123     char const *data() const
00124     {
00125         if (_tag & Direct_data)
00126         {
00127             union T { char const *d; char v[sizeof(char const *)]; };
00128             return reinterpret_cast<T const *>(&_d)->v;
00129         }
00130         return _d;
00131     }
00132
00134 #if __cplusplus >= 201103L

```

```

00135     Varg() = default;
00136 #else
00137     Varg() {}
00138 #endif
00139
00141     Varg(L4_varg_type t, void const *v, int len)
00142     : _tag(t | (static_cast<L4_mword_t>(len) << 16)),
00143       _d(static_cast<char const *>(v))
00144     {}
00145
00146     static Varg nil() { return Varg(L4_VARG_TYPE_NIL, 0, 0); }
00147
00154     template< typename V >
00155     typename Va_type<V>::Ret_value value() const
00156     {
00157         if (_tag & Direct_data)
00158         {
00159             union X { char const *d; V v; };
00160             return reinterpret_cast<X const &>(_d).v;
00161         }
00162
00163         return Va_type<V>::value(_d);
00164     }
00165
00166
00168     template< typename T >
00169     bool is_of() const { return Va_type<T>::id() == type(); }
00170
00172     bool is_nil() const { return is_of<void>(); }
00173
00175     bool is_of_int() const
00176     { return (type() & ~L4_VARG_TYPE_SIGN) == L4_VARG_TYPE_UMWORD; }
00177
00184     template< typename T >
00185     bool get_value(typename Va_type<T>::Value *v) const
00186     {
00187         if (!is_of<T>())
00188             return false;
00189
00190         *v = this->value<T>();
00191         return true;
00192     }
00193
00195     template< typename T >
00196     void set_value(void const *d)
00197     {
00198         typedef Va_type<T> Vt;
00199         _tag = Vt::id() | (Vt::size(d) << 16);
00200         _d = static_cast<char const *>(d);
00201     }
00202
00204     template<typename T>
00205     void set_direct_value(T val, typename L4::Types::Enable_if<sizeof(T) <= sizeof(char const *)>,
00206                          bool::type = true)
00207     {
00208         static_assert(sizeof(T) <= sizeof(char const *), "direct Varg value too big");
00209         typedef Va_type<T> Vt;
00210         _tag = Vt::id() | (sizeof(T) << 16) | Direct_data;
00211         union X { char const *d; T v; };
00212         reinterpret_cast<X &>(_d).v = val;
00213     }
00215     template<typename T> explicit
00216     Varg(T const *data) { set_value<T>(data); }
00218     Varg(char const *data) { set_value<char const *>(data); }
00219
00221     template<typename T> explicit
00222     Varg(T data, typename L4::Types::Enable_if<sizeof(T) <= sizeof(char const *)>, bool::type = true)
00223     { set_direct_value<T>(data); }
00224 };
00225
00226
00227     template<typename T>
00228     class Varg_t : public Varg
00229     {
00230     public:
00231         typedef typename Va_type<T>::Value Value;
00232         explicit Varg_t(Value v) : Varg()
00233         { _data = v; set_value<T>(Va_type<T>::addr_of(_data)); }
00234
00235     private:
00236         Value _data;
00237     };
00238
00239     template<unsigned MAX = L4_UTCB_GENERIC_DATA_SIZE>
00240     class Varg_list;
00241

```

```

00253 class Varg_list_ref
00254 {
00255 private:
00256     template<unsigned T>
00257     friend class Varg_list;
00258
00260     class Iter_state
00261     {
00262     private:
00263         using M = l4_umword_t;
00264         using Mp = M const *;
00265         Mp _c;
00266         Mp _e;
00267
00269         Mp next_arg(Varg const &a) const
00270         {
00271             return _c + 1 + (Msg::align_to<M>(a.length()) / sizeof(M));
00272         }
00273
00274     public:
00276         Iter_state() : _c(nullptr), _e(nullptr) {}
00277
00279         Iter_state(Mp c, Mp e) : _c(c), _e(e)
00280         {}
00281
00283         bool valid() const
00284         { return _c && _c < _e; }
00285
00287         Mp begin() const { return _c; }
00288
00290         Mp end() const { return _e; }
00291
00296         Varg pop()
00297         {
00298             if (!valid())
00299                 return Varg::nil();
00300
00301             Varg a;
00302             a.tag(_c[0]);
00303             a.data(reinterpret_cast<char const *>(&_c[1]));
00304             _c = next_arg(a);
00305             if (_c > _e)
00306                 return Varg::nil();
00307
00308             return a;
00309         }
00310
00312         bool operator == (Iter_state const &o) const
00313         { return _c == o._c; }
00314
00316         bool operator != (Iter_state const &o) const
00317         { return _c != o._c; }
00318     };
00319
00320     Iter_state _s;
00321
00322 public:
00324     Varg_list_ref() = default;
00325
00332     Varg_list_ref(void const *start, void const *end)
00333     : _s(reinterpret_cast<l4_umword_t const *>(start),
00334         reinterpret_cast<l4_umword_t const *>(end))
00335     {}
00336
00338     class Iterator
00339     {
00340     private:
00341         Iter_state _s;
00342         Varg _a;
00343
00344     public:
00346         Iterator(Iter_state const &s)
00347         : _s(s)
00348         {
00349             _a = _s.pop();
00350         }
00351
00353         explicit operator bool () const
00354         { return !_a.is_nil(); }
00355
00357         Iterator &operator ++ ()
00358         {
00359             if (!_a.is_nil())
00360                 _a = _s.pop();
00361
00362             return *this;
00363         }

```

```

00364
00366     Varg operator * () const
00367     { return _a; }
00368
00370     bool equals(Iterator const &o) const
00371     {
00372         if (_a.is_nil() && o._a.is_nil())
00373             return true;
00374
00375         return _s == o._s;
00376     }
00377
00378     bool operator == (Iterator const &o) const
00379     { return equals(o); }
00380
00381     bool operator != (Iterator const &o) const
00382     { return !equals(o); }
00383 };
00384
00386     Varg pop_front()
00387     { return _s.pop(); }
00388
00390     Varg next()
00391     { L4_DEPRECATED("Use range for or pop_front.");
00392       return _s.pop(); }
00393
00395     Iterator begin() const
00396     { return Iterator(_s); }
00397
00399     Iterator end() const
00400     { return Iterator(Iter_state()); }
00401 };
00402
00410 template<unsigned MAX>
00411 class Varg_list : public Varg_list_ref
00412 {
00413     l4_umword_t data[MAX];
00414     Varg_list(Varg_list const &);
00415
00416 public:
00418     Varg_list(Varg_list_ref const &r)
00419     {
00420         if (!r._s.valid())
00421             return;
00422
00423         l4_umword_t const *rs = r._s.begin();
00424         unsigned c = r._s.end() - rs;
00425         for (unsigned i = 0; i < c; ++i)
00426             data[i] = rs[i];
00427
00428         this->_s = Iter_state(data, data + c);
00429     }
00430 };
00431
00432 namespace Msg {
00433 template<> struct Elem<Varg const *>
00434 {
00435     typedef Varg const *arg_type;
00436     typedef Varg_list_ref svr_type;
00437     typedef Varg_list_ref svr_arg_type;
00438     enum { Is_optional = false };
00439 };
00440
00442 template<> struct Is_valid_rpc_type<Varg> : L4::Types::False {};
00443 template<> struct Is_valid_rpc_type<Varg *> : L4::Types::False {};
00444 template<> struct Is_valid_rpc_type<Varg &> : L4::Types::False {};
00445 template<> struct Is_valid_rpc_type<Varg const &> : L4::Types::False {};
00446
00447 template<> struct Direction<Varg const *> : Dir_in {};
00448 template<> struct Class<Varg const *> : Cls_data {};
00449
00450 template<typename DIR, typename CLASS>
00451 struct Clnt_val_ops<Varg, DIR, CLASS>
00452 {
00453     template<>
00454     struct Clnt_val_ops<Varg, Dir_in, Cls_data> :
00455         Clnt_noops<Varg const &>
00456     {
00457         using Clnt_noops<Varg const &>::to_msg;
00458         static int to_msg(char *msg, unsigned offs, unsigned limit,
00459                           Varg const &a, Dir_in, Cls_data)
00460         {
00461             for (Varg const *i = &a; i->tag(); ++i)
00462             {
00463                 offs = align_to<l4_umword_t>(offs);
00464                 if (L4_UNLIKELY(!check_size<l4_umword_t>(offs, limit)))

```

```

00465         return -L4_MSGTOOLONG;
00466     *reinterpret_cast<l4_umword_t*>(msg + offs) = i->tag();
00467     offs += sizeof(l4_umword_t);
00468     if (L4_UNLIKELY(!check_size<char>(offs, limit, i->length())))
00469         return -L4_MSGTOOLONG;
00470     char const *d = i->data();
00471     for (unsigned x = 0; x < i->length(); ++x)
00472         msg[offs++] = *d++;
00473     }
00474
00475     return offs;
00476 }
00477 };
00478
00479 template<>
00480 struct Svr_val_ops<Varg_list_ref, Dir_in, Cls_data> :
00481     Svr_noops<Varg_list_ref>
00482 {
00483     using Svr_noops<Varg_list_ref>::to_svr;
00484     static int to_svr(char *msg, unsigned offset, unsigned limit,
00485                     Varg_list_ref &a, Dir_in, Cls_data)
00486     {
00487         unsigned start = align_to<l4_umword_t>(offset);
00488         unsigned offs;
00489         for (offs = start; offs < limit;)
00490         {
00491             unsigned noffs = align_to<l4_umword_t>(offs);
00492             if (L4_UNLIKELY(!check_size<l4_umword_t>(noffs, limit)))
00493                 break;
00494
00495             offs = noffs;
00496             Varg arg;
00497             arg.tag(*reinterpret_cast<l4_umword_t*>(msg + offs));
00498
00499             if (!arg.tag())
00500                 break;
00501
00502             offs += sizeof(l4_umword_t);
00503
00504             if (L4_UNLIKELY(!check_size<char>(offs, limit, arg.length())))
00505                 return -L4_MSGTOOLONG;
00506             offs += arg.length();
00507         }
00508
00509         a = Varg_list_ref(msg + start, msg + align_to<l4_umword_t>(offs));
00510         return offs;
00511     }
00512 };
00513 }
00514 }

```

## 16.486 limits

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00002 /*
00003  * Copyright (C) 2026 Kernkonzept GmbH.
00004  * Author(s): Frank Mehnert <frank.mehnert@kernkonzept.com>
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00008
00009 #pragma once
00010 #pragma GCC system_header
00011
00012 #include <stddef.h>
00013 #include <limits.h>
00014
00015 // unfortunately we cannot include <limits>
00016 namespace L4 { namespace Types {
00017
00018     template< typename T > struct numeric_limits;
00019     template<> struct numeric_limits<bool>
00020     {
00021         static constexpr bool min() { return false; }
00022         static constexpr bool max() { return true; }
00023     };
00024     template<> struct numeric_limits<char>
00025     {
00026         static constexpr signed char min() { return SCHAR_MIN; }
00027         static constexpr signed char max() { return SCHAR_MAX; }
00028     };
00029     template<> struct numeric_limits<unsigned char>
00030     {

```


```

00031     static constexpr unsigned char min() { return 0; }
00032     static constexpr unsigned char max() { return UCHAR_MAX; }
00033 };
00034 template<> struct numeric_limits<signed short int>
00035 {
00036     static constexpr signed short int min() { return SHRT_MIN; }
00037     static constexpr signed short int max() { return SHRT_MAX; }
00038 };
00039 template<> struct numeric_limits<unsigned short int>
00040 {
00041     static constexpr unsigned short int min() { return 0; }
00042     static constexpr unsigned short int max() { return USHRT_MAX; }
00043 };
00044 template<> struct numeric_limits<signed int>
00045 {
00046     static constexpr signed int min() { return INT_MIN; }
00047     static constexpr signed int max() { return INT_MAX; }
00048 };
00049 template<> struct numeric_limits<unsigned int>
00050 {
00051     static constexpr unsigned int min() { return 0U; }
00052     static constexpr unsigned int max() { return UINT_MAX; }
00053 };
00054 template<> struct numeric_limits<signed long int>
00055 {
00056     static constexpr signed long min() { return LONG_MIN; }
00057     static constexpr signed long max() { return LONG_MAX; }
00058 };
00059 template<> struct numeric_limits<unsigned long int>
00060 {
00061     static constexpr unsigned long int min() { return 0UL; }
00062     static constexpr unsigned long int max() { return ULONG_MAX; }
00063 };
00064 template<> struct numeric_limits<signed long long int>
00065 {
00066     static constexpr signed long long min() { return LLONG_MIN; }
00067     static constexpr signed long long max() { return LLONG_MAX; }
00068 };
00069 template<> struct numeric_limits<unsigned long long int>
00070 {
00071     static constexpr unsigned long long min() { return 0ULL; }
00072     static constexpr unsigned long long max() { return ULLONG_MAX; }
00073 };
00074 template<> struct numeric_limits<l4_msgtag_t>
00075 {
00076     static constexpr long min() { return -max() - 1L; }
00077     static constexpr long max() { return numeric_limits<long>::max() >> 16; }
00078 };
00079
00080 }} // namespace Types, namespace L4
00081

```



```
#include <l4/sys/capability>
Include dependency graph for smart_capability_1x:
```

[illegible]

- namespace **L4**  
*L4 low-level kernel interface.*

## 16.488 smart\_capability\_1x

[Go to the documentation of this file.](#)

```

00001 // vim:set ft=cpp: -*- Mode: C++ -*-
00002 /*
00003  * (c) 2017 Alexander Warg <alexander.warg@kernkonzept.com>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007
00008 #pragma once
00009
00010 #include <l4/sys/capability>
00011
00012 namespace L4 { namespace Detail {
00013
00014     template< typename T, typename IMPL >
00015     class Smart_cap_base : public Cap_base, protected IMPL
00016     {
00017     protected:
00018         template<typename X>
00019         static IMPL &impl(Smart_cap_base<X, IMPL> &o) { return o; }
00020
00021         template<typename X>
00022         static IMPL const &impl(Smart_cap_base<X, IMPL> const &o) { return o; }
00023
00024     public:
00025         template<typename X, typename I>
00026         friend class ::L4::Detail::Smart_cap_base;
00027
00028         Smart_cap_base(Smart_cap_base const &) = delete;
00029         Smart_cap_base &operator = (Smart_cap_base const &) = delete;
00030
00031         Smart_cap_base() noexcept : Cap_base(Invalid) {}
00032
00033         explicit Smart_cap_base(Cap_base::Cap_type t) noexcept
00034         : Cap_base(t)
00035         {}
00036
00037         template<typename O>
00038         explicit constexpr Smart_cap_base(Cap<O> c) noexcept
00039         : Cap_base(c.cap())
00040         {}
00041
00042         template<typename O>
00043         explicit constexpr Smart_cap_base(Cap<O> c, IMPL const &impl) noexcept
00044         : Cap_base(c.cap()), IMPL(impl)
00045         {}
00046
00047         Cap<T> release() noexcept
00048         {
00049             l4_cap_idx_t c = this->cap();
00050             IMPL::invalidate(*this);
00051             return Cap<T>(c);
00052         }
00053
00054         void reset()
00055         { IMPL::free(*this); }
00056
00057         Cap<T> operator -> () const noexcept { return Cap<T>(this->cap()); }
00058         Cap<T> get() const noexcept { return Cap<T>(this->cap()); }
00059         ~Smart_cap_base() noexcept { IMPL::free(*this); }
00060     };
00061
00062     template< typename T, typename IMPL >
00063     class Unique_cap_impl final : public Smart_cap_base<T, IMPL>
00064     {
00065     private:
00066         typedef Smart_cap_base<T, IMPL> Base;
00067
00068     public:
00069         using Base::Base;
00070         Unique_cap_impl() noexcept = default;
00071
00072         Unique_cap_impl(Unique_cap_impl &&o) noexcept
00073         : Base(o.release(), Base::impl(o))
00074         {}
00075
00076         template<typename O>
00077         Unique_cap_impl(Unique_cap_impl<O, IMPL> &&o) noexcept
00078         : Base(o.release(), Base::impl(o))
00079         { Cap<T>::template check_convertible_from<O>(); }
00080
00081         Unique_cap_impl &operator = (Unique_cap_impl &&o) noexcept

```

```

00087 {
00088     if (&o == this)
00089         return *this;
00090
00091     IMPL::free(*this);
00092     this->_c = o.release().cap();
00093     this->IMPL::operator = (Base::impl(o));
00094     return *this;
00095 }
00096
00097 template<typename O>
00098 Unique_cap_impl &operator = (Unique_cap_impl<O, IMPL> &o) noexcept
00099 {
00100     Cap<T>::template check_convertible_from<O>();
00101
00102     IMPL::free(*this);
00103     this->_c = o.release().cap();
00104     this->IMPL::operator = (Base::impl(o));
00105     return *this;
00106 }
00107 };
00108
00109 template<typename T, typename IMPL>
00110 class Shared_cap_impl final : public Smart_cap_base<T, IMPL>
00111 {
00112 private:
00113     typedef Smart_cap_base<T, IMPL> Base;
00114
00115 public:
00116     using Base::Base;
00117     Shared_cap_impl() noexcept = default;
00118
00119     Shared_cap_impl(Shared_cap_impl &o) noexcept
00120     : Base(o.release(), Base::impl(o))
00121     {}
00122
00123     template<typename O>
00124     Shared_cap_impl(Shared_cap_impl<O, IMPL> &o) noexcept
00125     : Base(o.release(), Base::impl(o))
00126     { Cap<T>::template check_convertible_from<O>(); }
00127
00128     Shared_cap_impl &operator = (Shared_cap_impl &o) noexcept
00129     {
00130         if (&o == this)
00131             return *this;
00132
00133         IMPL::free(*this);
00134         this->_c = o.release().cap();
00135         this->IMPL::operator = (Base::impl(o));
00136         return *this;
00137     }
00138
00139     template<typename O>
00140     Shared_cap_impl &operator = (Shared_cap_impl<O, IMPL> &o) noexcept
00141     {
00142         Cap<T>::template check_convertible_from<O>();
00143
00144         IMPL::free(*this);
00145         this->_c = o.release().cap();
00146         this->IMPL::operator = (Base::impl(o));
00147         return *this;
00148     }
00149
00150     Shared_cap_impl(Shared_cap_impl const &o) noexcept
00151     : Base()
00152     {
00153         this->IMPL::operator = (Base::impl(o));
00154         this->_c = IMPL::copy(o).cap();
00155     }
00156
00157     template<typename O>
00158     Shared_cap_impl(Shared_cap_impl<O, IMPL> const &o) noexcept
00159     : Base()
00160     {
00161         Cap<T>::template check_convertible_from<O>();
00162         this->IMPL::operator = (Base::impl(o));
00163         this->_c = IMPL::copy(o).cap();
00164     }
00165
00166     Shared_cap_impl &operator = (Shared_cap_impl const &o) noexcept
00167     {
00168         if (&o == this)
00169             return *this;
00170
00171         IMPL::free(*this);
00172         this->IMPL::operator = (static_cast<IMPL const &>(o));
00173         this->_c = this->IMPL::copy(o).cap();

```


```

00174     return *this;
00175 }
00176
00177 template<typename O>
00178 Shared_cap_impl &operator = (Shared_cap_impl<O, IMPL> const &o) noexcept
00179 {
00180     Cap<T>::template check_convertible_from<O>();
00181     IMPL::free(*this);
00182     this->IMPL::operator = (static_cast<IMPL const &>(o));
00183     this->_c = this->IMPL::copy(o).cap();
00184     return *this;
00185 }
00186 };
00187
00188 }} // L4::Detail

```

## 16.489 l4/sys/cxx/types File Reference

This graph shows which files directly or indirectly include this file:



### Data Structures

- class [L4::Types::Flags< BITS\\_ENUM, UNDERLYING >](#)  
Template for defining typical *Flags* bitmaps.
- struct [L4::Types::Int\\_for\\_type< T >](#)  
Metafunction to get an integral type of the same size as *T*.
- struct [L4::Types::Flags\\_ops\\_t< DT >](#)  
Mixin class to define a set of friend bitwise operators on *DT*.
- struct [L4::Types::Flags\\_t< DT, T >](#)  
Template type to define a flags type with bitwise operations.
- struct [L4::Types::\\_\\_Add\\_rvalue\\_reference\\_helper< T, typename >](#)  
Helper template for *Add\_rvalue\_reference*.
- struct [L4::Types::\\_\\_Add\\_rvalue\\_reference\\_helper< T, Void< T && > >](#)  
Helper template for *Add\_rvalue\_reference*.
- struct [L4::Types::Add\\_rvalue\\_reference< T >](#)  
Create an rvalue reference of the given type.
- struct [L4::Types::Bool< V >](#)  
Boolean meta type.
- struct [L4::Types::False](#)  
*False* meta value.
- struct [L4::Types::True](#)  
*True* meta value.
- struct [L4::Types::Integral\\_constant< T, Value >](#)  
Wrapper for a static constant of the given type.
- struct [L4::Types::Is\\_enum< T >](#)  
Check whether the given type is an enumeration type.

- struct [L4::Types::\\_\\_Underlying\\_type\\_helper< T, bool >](#)  
*Helper template for [Underlying\\_type](#).*
- struct [L4::Types::\\_\\_Underlying\\_type\\_helper< T, false >](#)  
*Helper template for [Underlying\\_type](#).*
- struct [L4::Types::Underlying\\_type< T >](#)  
*Get an underlying type of an enumeration type.*
- struct [L4::Types::Same< A, B >](#)  
*Compare two data types for equality.*
- struct [Enum\\_bitops::Has\\_marker< typename, typename >](#)  
*Marker for the opt-in ADL function.*
- struct [Enum\\_bitops::Has\\_marker< T, Void< decltype\(enum\\_bitops\\_enable\(declval< T >\(\)\)\)> >](#)  
*Marker for the opt-in ADL function.*
- struct [Enum\\_bitops::Enable< T >](#)  
*Check whether the given enum type opts in for the bitwise operators.*

## Namespaces

- namespace [L4](#)  
*[L4](#) low-level kernel interface.*
- namespace [L4::Types](#)  
*[L4](#) basic type helpers for C++.*
- namespace [Enum\\_bitops](#)  
*Mechanism to opt-in for enum bitwise operators.*
- namespace [Enum\\_bitops\\_impl](#)  
*Bitwise operators on enumeration types.*

## Typedefs

- template<typename...>  
using [L4::Types::Void](#) = void  
*Map a sequence of any types to the void type.*
- template<typename T>  
using [L4::Types::Add\\_rvalue\\_reference\\_t](#) = typename [Add\\_rvalue\\_reference](#)<T>::type  
*Helper type for the [Add\\_rvalue\\_reference](#).*
- template<typename T>  
using [L4::Types::Underlying\\_type\\_t](#) = typename [Underlying\\_type](#)<T>::type  
*Helper type for [Underlying\\_type](#).*
- template<bool Condition, typename T = void>  
using [L4::Types::Enable\\_if\\_t](#) = typename [Enable\\_if](#)<Condition, T>::type  
*Helper type for [Enable\\_if](#).*

## Functions

- template<typename T>  
[Add\\_rvalue\\_reference\\_t](#)< T > [L4::Types::declval](#) () noexcept  
*Template for writing typed expressions in unevaluated contexts.*
- template<typename T, typename = [L4::Types::Enable\\_if\\_t](#)<[L4::Types::Is\\_enum](#)<T>::value>>  
constexpr [L4::Types::Underlying\\_type\\_t](#)< T > [Enum\\_bitops\\_impl::to\\_underlying](#) (T const arg) noexcept  
*Convert enum value to its underlying type value.*

- `template<typename T, typename = L4::Types::Enable_if_t<Enum_bitops::Enable<T>::value>>`  
`constexpr T Enum_bitops_impl::operator~ (T const a) noexcept`  
*Negate enum value.*
- `template<typename T, typename = L4::Types::Enable_if_t<Enum_bitops::Enable<T>::value>>`  
`constexpr T Enum_bitops_impl::operator& (T l, T r) noexcept`  
*Intersect enum values.*
- `template<typename T, typename = L4::Types::Enable_if_t<Enum_bitops::Enable<T>::value>>`  
`constexpr T & Enum_bitops_impl::operator&= (T &a, T const b) noexcept`  
*Intersect and assign enum values.*
- `template<typename T, typename = L4::Types::Enable_if_t<Enum_bitops::Enable<T>::value>>`  
`constexpr T Enum_bitops_impl::operator| (T l, T r) noexcept`  
*Union enum values.*
- `template<typename T, typename = L4::Types::Enable_if_t<Enum_bitops::Enable<T>::value>>`  
`constexpr T & Enum_bitops_impl::operator|= (T &a, T const b) noexcept`  
*Union and assign enum values.*
- `template<typename T, typename = L4::Types::Enable_if_t<Enum_bitops::Enable<T>::value>>`  
`constexpr T Enum_bitops_impl::operator- (T l, T r) noexcept`  
*Difference (intersect with negation, clear bits) enum values.*
- `template<typename T, typename = L4::Types::Enable_if_t<Enum_bitops::Enable<T>::value>>`  
`constexpr T & Enum_bitops_impl::operator-= (T &a, T const b) noexcept`  
*Difference (intersect with negation, clear bits) and assign enum values.*

## 16.490 types

[Go to the documentation of this file.](#)

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00002 /*
00003  * (c) 2014 Alexander Warg <alexander.warg@kernkonzept.com>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007
00009
00010 #pragma once
00011
00012 // very simple type traits for basic L4 functions, for a more complete set
00013 // use <l4/cxx/type_traits> or the standard <type_traits>.
00014
00015 namespace L4 {
00016
00020 namespace Types {
00021
00051     template<typename BITS_ENUM, typename UNDERLYING = unsigned long>
00052     class Flags
00053     {
00054     public:
00056         typedef UNDERLYING value_type;
00058         typedef BITS_ENUM bits_enum_type;
00060         typedef Flags<BITS_ENUM, UNDERLYING> type;
00061
00062     private:
00063         value_type _v;
00064         explicit constexpr Flags(value_type v) : _v(v) {}
00065
00066     public:
00068         enum None_type { None };
00069
00078         constexpr Flags(None_type) : _v(0) {}
00079
00081         constexpr Flags() : _v(0) {}
00082
00091         constexpr Flags(BITS_ENUM e) : _v((value_type{1}) << e) {}
00092
00098         static constexpr type from_raw(value_type v) { return type(v); }
00099
00101         explicit constexpr operator bool () const
00102         { return _v != 0; }
00103

```

```

00105     constexpr bool operator ! () const { return _v == 0; }
00106
00108     friend constexpr type operator | (type lhs, type rhs)
00109     { return type(lhs._v | rhs._v); }
00110
00112     friend constexpr type operator | (type lhs, bits_enum_type rhs)
00113     { return lhs | type(rhs); }
00114
00116     friend constexpr type operator & (type lhs, type rhs)
00117     { return type(lhs._v & rhs._v); }
00118
00120     friend constexpr type operator & (type lhs, bits_enum_type rhs)
00121     { return lhs & type(rhs); }
00122
00124     constexpr type &operator |= (type rhs) { _v |= rhs._v; return *this; }
00125
00127     constexpr type &operator |= (bits_enum_type rhs)
00128     { return operator |= (type(rhs)); }
00129
00131     constexpr type &operator &= (type rhs) { _v &= rhs._v; return *this; }
00132
00134     constexpr type &operator &= (bits_enum_type rhs)
00135     { return operator &= (type(rhs)); }
00136
00138     constexpr type operator ~ () const { return type(~_v); }
00139
00146     constexpr type &clear(bits_enum_type flag)
00147     { return operator &= (~type(flag)); }
00148
00150     constexpr value_type as_value() const { return _v; }
00151 };
00152
00158 template<unsigned SIZE, bool = true> struct Int_for_size;
00159
00160 template<> struct Int_for_size<sizeof(unsigned char), true>
00161 { typedef unsigned char type; };
00162
00163 template<> struct Int_for_size<sizeof(unsigned short),
00164                             (sizeof(unsigned short) > sizeof(unsigned char))>
00165 { typedef unsigned short type; };
00166
00167 template<> struct Int_for_size<sizeof(unsigned),
00168                             (sizeof(unsigned) > sizeof(unsigned short))>
00169 { typedef unsigned type; };
00170
00171 template<> struct Int_for_size<sizeof(unsigned long),
00172                             (sizeof(unsigned long) > sizeof(unsigned))>
00173 { typedef unsigned long type; };
00174
00175 template<> struct Int_for_size<sizeof(unsigned long long),
00176                             (sizeof(unsigned long long) > sizeof(unsigned long))>
00177 { typedef unsigned long long type; };
00178
00185 template<typename T> struct Int_for_type
00186 {
00190     typedef typename Int_for_size<sizeof(T)>::type type;
00191 };
00192
00199 template<typename DT>
00200 struct Flags_ops_t
00201 {
00203     friend constexpr DT operator | (DT l, DT r)
00204     { return DT(l.raw | r.raw); }
00205
00207     friend constexpr DT operator & (DT l, DT r)
00208     { return DT(l.raw & r.raw); }
00209
00211     friend constexpr DT operator ~ (DT l, DT r)
00212     { return DT(l.raw & ~r.raw); }
00213
00215     friend constexpr bool operator == (DT l, DT r)
00216     { return l.raw == r.raw; }
00217
00219     friend constexpr bool operator != (DT l, DT r)
00220     { return l.raw != r.raw; }
00221
00223     constexpr DT &operator |= (DT const r)
00224     {
00225         static_cast<DT *>(this)->raw |= r.raw;
00226         return *static_cast<DT *>(this);
00227     }
00228
00230     constexpr DT &operator &= (DT const r)
00231     {
00232         static_cast<DT *>(this)->raw &= r.raw;
00233         return *static_cast<DT *>(this);
00234     }

```

```

00235
00237     constexpr DT &operator -= (DT const r)
00238     {
00239         static_cast<DT *>(this)->raw &= ~r.raw;
00240         return *static_cast<DT *>(this);
00241     }
00242
00244     explicit constexpr operator bool () const
00245     { return static_cast<DT const *>(this)->raw != 0; }
00246
00248     constexpr DT operator ~ () const
00249     { return DT(~static_cast<DT const *>(this)->raw); }
00250 };
00251
00260 template<typename DT, typename T>
00261 struct Flags_t : Flags_ops_t<Flags_t<DT, T>
00262 {
00264     T raw = 0;
00266     constexpr Flags_t() = default;
00268     constexpr Flags_t(DT f) : raw(static_cast<T>(f)) {}
00270     explicit constexpr Flags_t(T f) : raw(f) {}
00271
00273     static constexpr Flags_t None = Flags_t();
00274 };
00275
00277 template<typename...> using Void = void;
00278
00280 template<typename T, typename = void> struct __Add_rvalue_reference_helper
00281 { using type = T; };
00282
00284 template<typename T> struct __Add_rvalue_reference_helper<T, Void<T &&>>
00285 { using type = T &&; };
00286
00288 template<typename T> struct Add_rvalue_reference
00289 { using type = typename __Add_rvalue_reference_helper<T>::type; };
00290
00292 template<typename T> using Add_rvalue_reference_t
00293     = typename Add_rvalue_reference<T>::type;
00294
00303 template<typename T> Add_rvalue_reference_t<T> declval() noexcept;
00304
00310 template< bool V > struct Bool
00311 {
00312     typedef Bool<V> type;
00313     enum { value = V };
00314 };
00315
00318 struct False : Bool<false> {};
00319
00322 struct True : Bool<true> {};
00323
00325 template<typename T, T Value>
00326 struct Integral_constant
00327 {
00328     static T const value = Value;
00329
00330     typedef T value_type;
00331     typedef Integral_constant<T, Value> type;
00332 };
00333
00345 template<typename T>
00346 struct Is_enum : Integral_constant<bool, __is_enum(T)> {};
00347
00359 template<typename T, bool = Is_enum<T>::value>
00360 struct __Underlying_type_helper { using type = __underlying_type(T); };
00361
00363 template<typename T> struct __Underlying_type_helper<T, false> {};
00364
00366 template<typename T> struct Underlying_type
00367     : public __Underlying_type_helper<T> {};
00368
00370 template<typename T> using Underlying_type_t
00371     = typename Underlying_type<T>::type;
00372
00373 /*****/
00382 template<typename A, typename B>
00383 struct Same : False {};
00384
00386 template<typename A>
00387 struct Same<A, A> : True {};
00388
00388 template<bool, typename = void> struct Enable_if {};
00389 template<typename T> struct Enable_if<true, T> { typedef T type; };
00390
00392 template<bool Condition, typename T = void>
00393     using Enable_if_t = typename Enable_if<Condition, T>::type;
00394

```



```

00395     template<typename T1, typename T2, typename T = void>
00396     struct Enable_if_same : Enable_if<Same<T1, T2>::value, T> {};
00397
00398     template<typename T> struct Remove_const { typedef T type; };
00399     template<typename T> struct Remove_const<T const> { typedef T type; };
00400     template<typename T> struct Remove_volatile { typedef T type; };
00401     template<typename T> struct Remove_volatile<T volatile> { typedef T type; };
00402     template<typename T> struct Remove_cv
00403     { typedef typename Remove_const<typename Remove_volatile<T>::type>::type type; };
00404
00405     template<typename T> struct Remove_pointer { typedef T type; };
00406     template<typename T> struct Remove_pointer<T*> { typedef T type; };
00407     template<typename T> struct Remove_reference { typedef T type; };
00408     template<typename T> struct Remove_reference<T&> { typedef T type; };
00409     template<typename T> struct Remove_pr { typedef T type; };
00410     template<typename T> struct Remove_pr<T&> { typedef T type; };
00411     template<typename T> struct Remove_pr<T*> { typedef T type; };
00412 } // Types
00413
00414 } // L4
00415
00427 namespace Enum_bitops {
00428     using namespace L4::Types;
00429
00431     template<typename, typename = void> struct Has_marker : False {};
00432
00434     template<typename T>
00435     struct Has_marker<T, Void<decltype(enum_bitops_enable(declval<T>()))>
00436         : True {};
00437
00439     template<typename T>
00440     struct Enable
00441         : Integral_constant<bool, Is_enum<T>::value && Has_marker<T>::value> {};
00442 } // Enum_bitops
00443
00455 inline namespace Enum_bitops_impl {
00457     template<typename T,
00458         typename = L4::Types::Enable_if_t<L4::Types::Is_enum<T>::value>
00459     constexpr L4::Types::Underlying_type_t<T> to_underlying(T const arg) noexcept
00460     { return static_cast<L4::Types::Underlying_type_t<T>>(arg); }
00461
00463     template<typename T,
00464         typename = L4::Types::Enable_if_t<Enum_bitops::Enable<T>::value>
00465     constexpr T operator ~ (T const a) noexcept
00466     { return static_cast<T>(~to_underlying(a)); }
00467
00469     template<typename T,
00470         typename = L4::Types::Enable_if_t<Enum_bitops::Enable<T>::value>
00471     constexpr T operator & (T l, T r) noexcept
00472     { return static_cast<T>(to_underlying(l) & to_underlying(r)); }
00473
00475     template<typename T,
00476         typename = L4::Types::Enable_if_t<Enum_bitops::Enable<T>::value>
00477     constexpr T &operator &= (T &a, T const b) noexcept
00478     {
00479         a = a & b;
00480         return a;
00481     }
00482
00484     template<typename T,
00485         typename = L4::Types::Enable_if_t<Enum_bitops::Enable<T>::value>
00486     constexpr T operator | (T l, T r) noexcept
00487     { return static_cast<T>(to_underlying(l) | to_underlying(r)); }
00488
00490     template<typename T,
00491         typename = L4::Types::Enable_if_t<Enum_bitops::Enable<T>::value>
00492     constexpr T &operator |= (T &a, T const b) noexcept
00493     {
00494         a = a | b;
00495         return a;
00496     }
00497
00499     template<typename T,
00500         typename = L4::Types::Enable_if_t<Enum_bitops::Enable<T>::value>
00501     constexpr T operator - (T l, T r) noexcept
00502     { return static_cast<T>(to_underlying(l) & ~to_underlying(r)); }
00503
00505     template<typename T,
00506         typename = L4::Types::Enable_if_t<Enum_bitops::Enable<T>::value>
00507     constexpr T &operator -= (T &a, T const b) noexcept
00508     {
00509         a = a - b;
00510         return a;
00511     }
00512 } // Enum_bitops_impl

```



## 16.492 debugger

[Go to the documentation of this file.](#)

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00002 /*
00003  * (c) 2010-2011 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00004  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00005  *      economic rights: Technische Universität Dresden (Germany)
00006  *
00007  * License: see LICENSE.spdx (in this directory or the directories above)
00008  */
00009 #pragma once
00010
00011 #include <l4/sys/debugger.h>
00012 #include <l4/sys/kobject>
00013
00014 namespace L4 {
00015
00016 class Debugger : public Kobject_t<Debugger, Kobject, L4_PROTO_DEBUGGER>
00017 {
00018 public:
00019     enum
00020     {
00021         Switch_log_on = L4_DEBUGGER_SWITCH_LOG_ON,
00022         Switch_log_off = L4_DEBUGGER_SWITCH_LOG_OFF,
00023     };
00024
00025     l4_msgtag_t set_object_name(const char *name,
00026                                l4_utcb_t *utcb = l4_utcb()) noexcept
00027     { return l4_debugger_set_object_name_u(cap(), name, utcb); }
00028
00029     unsigned long global_id(l4_utcb_t *utcb = l4_utcb()) noexcept
00030     { return l4_debugger_global_id_u(cap(), utcb); }
00031
00032     unsigned long kobj_to_id(l4_addr_t kobjp,
00033                              l4_utcb_t *utcb = l4_utcb()) noexcept
00034     { return l4_debugger_kobj_to_id_u(cap(), kobjp, utcb); }
00035
00036     l4_ret_t query_log_typeid(const char *name, unsigned idx,
00037                               l4_utcb_t *utcb = l4_utcb()) noexcept
00038     { return l4_debugger_query_log_typeid_u(cap(), name, idx, utcb); }
00039
00040     l4_ret_t query_log_name(unsigned idx,
00041                              char *name, unsigned namelen,
00042                              char *shortname, unsigned shortnamelen,
00043                              l4_utcb_t *utcb = l4_utcb()) noexcept
00044     { return l4_debugger_query_log_name_u(cap(), idx, name, namelen,
00045                                           shortname, shortnamelen, utcb); }
00046
00047     l4_msgtag_t switch_log(const char *name, unsigned on_off,
00048                            l4_utcb_t *utcb = l4_utcb()) noexcept
00049     { return l4_debugger_switch_log_u(cap(), name, on_off, utcb); }
00050
00051     l4_msgtag_t query_object_name(unsigned id, char *name, unsigned size,
00052                                    l4_utcb_t *utcb = l4_utcb()) noexcept
00053     { return l4_debugger_query_object_name_u(cap(), id, name, size, utcb); }
00054
00055     l4_msgtag_t get_object_name(char *name, unsigned size,
00056                                 l4_utcb_t *utcb = l4_utcb()) noexcept
00057     { return l4_debugger_get_object_name_u(cap(), name, size, utcb); }
00058
00059     l4_msgtag_t add_image_info(l4_addr_t base, const char *name,
00060                                l4_utcb_t *utcb = l4_utcb()) noexcept
00061     { return l4_debugger_add_image_info_u(cap(), base, name, utcb); }
00062 };
00063
00064 }
```


## 16.493 l4/sys/debugger.h File Reference

Debugger related definitions.


```

#include <l4/sys/compiler.h>
#include <l4/sys/utcb.h>
#include <l4/sys/ipc.h>
```

```
#include <l4/sys/kernel_object.h>
Include dependency graph for debugger.h:
```



This graph shows which files directly or indirectly include this file:



## Enumerations

- enum {  
L4\_DEBUGGER\_KOBJ\_SET\_NAME\_OP = 0UL , L4\_DEBUGGER\_KOBJ\_GET\_GLOBAL\_ID\_OP = 1UL ,  
L4\_DEBUGGER\_KOBJ\_PTR\_GET\_GLOBAL\_ID\_OP = 2UL , L4\_DEBUGGER\_LOG\_QUERY\_TYPEID\_OP  
= 3UL ,  
L4\_DEBUGGER\_LOG\_SWITCH\_OP = 4UL , L4\_DEBUGGER\_GLOBAL\_ID\_GET\_NAME\_OP = 5UL ,

```

L4_DEBUGGER_LOG_QUERY_NAME_OP = 6UL , L4_DEBUGGER_TASK_ADD_IMAGE_INFO_OP =
7UL ,
L4_DEBUGGER_KOBJ_GET_NAME_OP = 8UL , L4_DEBUGGER_OBJ_INFO_OP = 16UL }

```

## Functions

- [l4\\_msgtag\\_t l4\\_debugger\\_set\\_object\\_name](#) ([l4\\_cap\\_idx\\_t](#) cap, const char \*name) [L4\\_NOTHROW](#)  
*Set the name of a kernel object.*
- [l4\\_msgtag\\_t l4\\_debugger\\_query\\_object\\_name](#) ([l4\\_cap\\_idx\\_t](#) cap, unsigned id, char \*name, unsigned size) [L4\\_NOTHROW](#)  
*Get name of the kernel object with id id.*
- [l4\\_msgtag\\_t l4\\_debugger\\_get\\_object\\_name](#) ([l4\\_cap\\_idx\\_t](#) cap, char \*name, unsigned size) [L4\\_NOTHROW](#)  
*Get name of a kernel object.*
- unsigned long [l4\\_debugger\\_global\\_id](#) ([l4\\_cap\\_idx\\_t](#) cap) [L4\\_NOTHROW](#)  
*Get the globally unique ID of the object behind a capability.*
- unsigned long [l4\\_debugger\\_kobj\\_to\\_id](#) ([l4\\_cap\\_idx\\_t](#) cap, [l4\\_addr\\_t](#) kobjp) [L4\\_NOTHROW](#)  
*Get the globally unique ID of the object behind the kobject pointer.*
- [l4\\_ret\\_t l4\\_debugger\\_query\\_log\\_typeid](#) ([l4\\_cap\\_idx\\_t](#) cap, const char \*name, unsigned idx) [L4\\_NOTHROW](#)  
*Query the log-id for a log type.*
- [l4\\_ret\\_t l4\\_debugger\\_query\\_log\\_name](#) ([l4\\_cap\\_idx\\_t](#) cap, unsigned idx, char \*name, unsigned namelen, char \*shortname, unsigned shortnamelen) [L4\\_NOTHROW](#)  
*Query the name of a log type given the ID.*
- [l4\\_msgtag\\_t l4\\_debugger\\_switch\\_log](#) ([l4\\_cap\\_idx\\_t](#) cap, const char \*name, int on\_off) [L4\\_NOTHROW](#)  
*Set or unset log.*
- [l4\\_msgtag\\_t l4\\_debugger\\_add\\_image\\_info](#) ([l4\\_cap\\_idx\\_t](#) cap, [l4\\_addr\\_t](#) base, const char \*name) [L4\\_NOTHROW](#)  
*Add loaded image information for a task.*

## 16.493.1 Detailed Description

Debugger related definitions.

Definition in file [debugger.h](#).

## 16.493.2 Enumeration Type Documentation

### 16.493.2.1 anonymous enum

anonymous enum

#### Enumerator

L4_DEBUGGER_KOBJ_SET_NAME_OP	Set debug name of kernel object.
L4_DEBUGGER_KOBJ_GET_GLOBAL_ID_OP	Get debug ID of kernel object.
L4_DEBUGGER_KOBJ_PTR_GET_GLOBAL_ID_OP	Get debug ID of kernel object by pointer.
L4_DEBUGGER_LOG_QUERY_TYPEID_OP	Query log-id for log type.
L4_DEBUGGER_LOG_SWITCH_OP	Enable / disable log.

L4_DEBUGGER_GLOBAL_ID_GET_NAME_OP	Get debug name of kernel object by debug ID.
L4_DEBUGGER_LOG_QUERY_NAME_OP	Get name of log type for given log-id.
L4_DEBUGGER_TASK_ADD_IMAGE_INFO_OP	Add image information for task.
L4_DEBUGGER_KOBJ_GET_NAME_OP	Get debug name of kernel object.
L4_DEBUGGER_OBJ_INFO_OP	Query information about all kernel objects.

Definition at line 234 of file [debugger.h](#).

## 16.494 debugger.h

[Go to the documentation of this file.](#)

```

00001 #pragma once
00002 /*
00003  * (c) 2008-2011 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00004  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00005  *      economic rights: Technische Universität Dresden (Germany)
00006  *
00007  * License: see LICENSE.spdx (in this directory or the directories above)
00008  */
00009
00010 #include <l4/sys/compiler.h>
00011 #include <l4/sys/utcb.h>
00012 #include <l4/sys/ipc.h>
00013
00014
00015 L4_INLINE l4_msgtag_t
00016 l4_debugger_set_object_name(l4_cap_idx_t cap, const char *name) L4_NOTHROW;
00017
00018 L4_INLINE l4_msgtag_t
00019 l4_debugger_set_object_name_u(l4_cap_idx_t cap, const char *name, l4_utcb_t *utcb) L4_NOTHROW;
00020
00021 L4_INLINE l4_msgtag_t
00022 l4_debugger_query_object_name(l4_cap_idx_t cap, unsigned id,
00023                               char *name, unsigned size) L4_NOTHROW;
00024
00025 L4_INLINE l4_msgtag_t
00026 l4_debugger_query_object_name_u(l4_cap_idx_t cap, unsigned id,
00027                                 char *name, unsigned size,
00028                                 l4_utcb_t *utcb) L4_NOTHROW;
00029
00030 L4_INLINE l4_msgtag_t
00031 l4_debugger_get_object_name(l4_cap_idx_t cap,
00032                             char *name, unsigned size) L4_NOTHROW;
00033
00034 L4_INLINE l4_msgtag_t
00035 l4_debugger_get_object_name_u(l4_cap_idx_t cap,
00036                               char *name, unsigned size,
00037                               l4_utcb_t *utcb) L4_NOTHROW;
00038
00039 L4_INLINE unsigned long
00040 l4_debugger_global_id(l4_cap_idx_t cap) L4_NOTHROW;
00041
00042 L4_INLINE unsigned long
00043 l4_debugger_global_id_u(l4_cap_idx_t cap, l4_utcb_t *utcb) L4_NOTHROW;
00044
00045 L4_INLINE unsigned long
00046 l4_debugger_kobj_to_id(l4_cap_idx_t cap, l4_addr_t kobjp) L4_NOTHROW;
00047
00048 L4_INLINE unsigned long
00049 l4_debugger_kobj_to_id_u(l4_cap_idx_t cap, l4_addr_t kobjp, l4_utcb_t *utcb) L4_NOTHROW;
00050
00051 L4_INLINE l4_ret_t
00052 l4_debugger_query_log_typeid(l4_cap_idx_t cap, const char *name,
00053                              unsigned idx) L4_NOTHROW;
00054
00055 L4_INLINE l4_ret_t
00056 l4_debugger_query_log_typeid_u(l4_cap_idx_t cap, const char *name,
00057                                unsigned idx, l4_utcb_t *utcb) L4_NOTHROW;
00058
00059 L4_INLINE l4_ret_t
00060 l4_debugger_query_log_name(l4_cap_idx_t cap, unsigned idx,
00061                            char *name, unsigned namelen,
00062                            char *shortname, unsigned shortnamelen) L4_NOTHROW;

```

```

00182
00186 L4_INLINE l4_ret_t
00187 l4_debugger_query_log_name_u(l4_cap_idx_t cap, unsigned idx,
00188                               char *name, unsigned namelen,
00189                               char *shortname, unsigned shortnamelen,
00190                               l4_utcb_t *utcb) L4_NOTHROW;
00191
00202 L4_INLINE l4_msgtag_t
00203 l4_debugger_switch_log(l4_cap_idx_t cap, const char *name,
00204                        int on_off) L4_NOTHROW;
00205
00209 L4_INLINE l4_msgtag_t
00210 l4_debugger_switch_log_u(l4_cap_idx_t cap, const char *name, int on_off,
00211                          l4_utcb_t *utcb) L4_NOTHROW;
00212
00223 L4_INLINE l4_msgtag_t
00224 l4_debugger_add_image_info(l4_cap_idx_t cap, l4_addr_t base,
00225                            const char *name) L4_NOTHROW;
00226
00230 L4_INLINE l4_msgtag_t
00231 l4_debugger_add_image_info_u(l4_cap_idx_t cap, l4_addr_t base, const char *name,
00232                              l4_utcb_t *utcb) L4_NOTHROW;
00233
00234 enum
00235 {
00237     L4_DEBUGGER_KOBJ_SET_NAME_OP = 0UL,
00239     L4_DEBUGGER_KOBJ_GET_GLOBAL_ID_OP = 1UL,
00241     L4_DEBUGGER_KOBJ_PTR_GET_GLOBAL_ID_OP = 2UL,
00243     L4_DEBUGGER_LOG_QUERY_TYPEID_OP = 3UL,
00245     L4_DEBUGGER_LOG_SWITCH_OP = 4UL,
00247     L4_DEBUGGER_GLOBAL_ID_GET_NAME_OP = 5UL,
00249     L4_DEBUGGER_LOG_QUERY_NAME_OP = 6UL,
00251     L4_DEBUGGER_TASK_ADD_IMAGE_INFO_OP = 7UL,
00253     L4_DEBUGGER_KOBJ_GET_NAME_OP = 8UL,
00254
00256     L4_DEBUGGER_OBJ_INFO_OP = 16UL,
00257 };
00258
00259 enum
00260 {
00261     L4_DEBUGGER_SWITCH_LOG_ON = 1,
00262     L4_DEBUGGER_SWITCH_LOG_OFF = 0,
00263 };
00264
00265 /* IMPLEMENTATION -----*/
00266
00267 #include <l4/sys/kernel_object.h>
00268
00282 L4_INLINE unsigned
00283 __strcpy_maxlen(char *dst, char const *src, unsigned maxlen)
00284 {
00285     unsigned i;
00286     if (!maxlen)
00287         return 0;
00288
00289     for (i = 0; i < maxlen - 1 && src[i]; ++i)
00290         dst[i] = src[i];
00291     dst[i] = '\0';
00292
00293     return i + 1;
00294 }
00295
00296 L4_INLINE l4_msgtag_t
00297 l4_debugger_set_object_name_u(l4_cap_idx_t cap,
00298                               const char *name, l4_utcb_t *utcb) L4_NOTHROW
00299 {
00300     unsigned i;
00301     l4_utcb_mr_u(utcb)->mr[0] = L4_DEBUGGER_KOBJ_SET_NAME_OP;
00302     i = __strcpy_maxlen((char *)&l4_utcb_mr_u(utcb)->mr[1], name,
00303                        (L4_UTCB_GENERIC_DATA_SIZE - 2) * sizeof(l4_umword_t));
00304     i = l4_bytes_to_mwords(i);
00305     return l4_invoke_debugger(cap, l4_msgtag(0, 1 + i, 0, 0), utcb);
00306 }
00307
00308 L4_INLINE unsigned long
00309 l4_debugger_global_id_u(l4_cap_idx_t cap, l4_utcb_t *utcb) L4_NOTHROW
00310 {
00311     l4_utcb_mr_u(utcb)->mr[0] = L4_DEBUGGER_KOBJ_GET_GLOBAL_ID_OP;
00312     if (l4_error_u(l4_invoke_debugger(cap, l4_msgtag(0, 1, 0, 0), utcb), utcb))
00313         return ~0UL;
00314     return l4_utcb_mr_u(utcb)->mr[0];
00315 }
00316
00317 L4_INLINE unsigned long
00318 l4_debugger_kobj_to_id_u(l4_cap_idx_t cap, l4_addr_t kobjp, l4_utcb_t *utcb) L4_NOTHROW
00319 {
00320     l4_utcb_mr_u(utcb)->mr[0] = L4_DEBUGGER_KOBJ_PTR_GET_GLOBAL_ID_OP;

```

```

00321     l4_utcb_mr_u(utcb)->mr[1] = kobjp;
00322     if (l4_error_u(l4_invoke_debugger(cap, l4_msgtag(0, 2, 0, 0), utcb), utcb))
00323         return ~0UL;
00324     return l4_utcb_mr_u(utcb)->mr[0];
00325 }
00326
00327 L4_INLINE l4_ret_t
00328 l4_debugger_query_log_typeid_u(l4_cap_idx_t cap, const char *name,
00329                                unsigned idx,
00330                                l4_utcb_t *utcb) L4_NOTHROW
00331 {
00332     unsigned i;
00333     l4_ret_t e;
00334     l4_utcb_mr_u(utcb)->mr[0] = L4_DEBUGGER_LOG_QUERY_TYPEID_OP;
00335     l4_utcb_mr_u(utcb)->mr[1] = idx;
00336     i = __strcpy_maxlen((char *)&l4_utcb_mr_u(utcb)->mr[2], name, 32);
00337     i = l4_bytes_to_mwords(i);
00338     e = l4_error_u(l4_invoke_debugger(cap, l4_msgtag(0, 2 + i, 0, 0), utcb), utcb);
00339     if (e < 0)
00340         return e;
00341     return l4_utcb_mr_u(utcb)->mr[0];
00342 }
00343
00344 L4_INLINE l4_ret_t
00345 l4_debugger_query_log_name_u(l4_cap_idx_t cap, unsigned idx,
00346                              char *name, unsigned namelen,
00347                              char *shortname, unsigned shortnamelen,
00348                              l4_utcb_t *utcb) L4_NOTHROW
00349 {
00350     l4_ret_t e;
00351     char const *n;
00352     l4_utcb_mr_u(utcb)->mr[0] = L4_DEBUGGER_LOG_QUERY_NAME_OP;
00353     l4_utcb_mr_u(utcb)->mr[1] = idx;
00354     e = l4_error_u(l4_invoke_debugger(cap, l4_msgtag(0, 2, 0, 0), utcb), utcb);
00355     if (e < 0)
00356         return e;
00357     n = (char const *)&l4_utcb_mr_u(utcb)->mr[0];
00358     __strcpy_maxlen(name, n, namelen);
00359     __strcpy_maxlen(shortname, n + __builtin_strlen(n) + 1, shortnamelen);
00360     return 0;
00361 }
00362
00363
00364 L4_INLINE l4_msgtag_t
00365 l4_debugger_switch_log_u(l4_cap_idx_t cap, const char *name, int on_off,
00366                          l4_utcb_t *utcb) L4_NOTHROW
00367 {
00368     unsigned i;
00369     l4_utcb_mr_u(utcb)->mr[0] = L4_DEBUGGER_LOG_SWITCH_OP;
00370     l4_utcb_mr_u(utcb)->mr[1] = on_off;
00371     i = __strcpy_maxlen((char *)&l4_utcb_mr_u(utcb)->mr[2], name, 32);
00372     i = l4_bytes_to_mwords(i);
00373     return l4_invoke_debugger(cap, l4_msgtag(0, 2 + i, 0, 0), utcb);
00374 }
00375
00376 L4_INLINE l4_msgtag_t
00377 l4_debugger_query_object_name_u(l4_cap_idx_t cap, unsigned id,
00378                                 char *name, unsigned size,
00379                                 l4_utcb_t *utcb) L4_NOTHROW
00380 {
00381     l4_msgtag_t t;
00382     l4_utcb_mr_u(utcb)->mr[0] = L4_DEBUGGER_GLOBAL_ID_GET_NAME_OP;
00383     l4_utcb_mr_u(utcb)->mr[1] = id;
00384     t = l4_invoke_debugger(cap, l4_msgtag(0, 2, 0, 0), utcb);
00385     __strcpy_maxlen(name, (char const *)&l4_utcb_mr_u(utcb)->mr[0], size);
00386     return t;
00387 }
00388
00389 L4_INLINE l4_msgtag_t
00390 l4_debugger_get_object_name_u(l4_cap_idx_t cap,
00391                               char *name, unsigned size,
00392                               l4_utcb_t *utcb) L4_NOTHROW
00393 {
00394     l4_msgtag_t t;
00395     l4_utcb_mr_u(utcb)->mr[0] = L4_DEBUGGER_KOBJ_GET_NAME_OP;
00396     t = l4_invoke_debugger(cap, l4_msgtag(0, 1, 0, 0), utcb);
00397     __strcpy_maxlen(name, (char const *)&l4_utcb_mr_u(utcb)->mr[0], size);
00398     return t;
00399 }
00400
00401 L4_INLINE l4_msgtag_t
00402 l4_debugger_add_image_info_u(l4_cap_idx_t cap, l4_addr_t base,
00403                             const char *name, l4_utcb_t *utcb) L4_NOTHROW
00404 {
00405     unsigned i;
00406     l4_utcb_mr_u(utcb)->mr[0] = L4_DEBUGGER_TASK_ADD_IMAGE_INFO_OP;
00407     l4_utcb_mr_u(utcb)->mr[1] = base;

```



```

00408     i = __strcpy_maxlen((char *)&l4_utcb_mr_u(utcb)->mr[2], name,
00409                         (L4_UTCB_GENERIC_DATA_SIZE - 3) * sizeof(l4_umword_t));
00410     i = l4_bytes_to_mwords(i);
00411     return l4_invoke_debugger(cap, l4_msgtag(0, 2 + i, 0, 0), utcb);
00412 }
00413
00414
00415 L4_INLINE l4_msgtag_t
00416 l4_debugger_set_object_name(l4_cap_idx_t cap,
00417                             const char *name) L4_NOTHROW
00418 {
00419     return l4_debugger_set_object_name_u(cap, name, l4_utcb());
00420 }
00421
00422 L4_INLINE unsigned long
00423 l4_debugger_global_id(l4_cap_idx_t cap) L4_NOTHROW
00424 {
00425     return l4_debugger_global_id_u(cap, l4_utcb());
00426 }
00427
00428 L4_INLINE unsigned long
00429 l4_debugger_kobj_to_id(l4_cap_idx_t cap, l4_addr_t kobjp) L4_NOTHROW
00430 {
00431     return l4_debugger_kobj_to_id_u(cap, kobjp, l4_utcb());
00432 }
00433
00434 L4_INLINE l4_ret_t
00435 l4_debugger_query_log_typeid(l4_cap_idx_t cap, const char *name,
00436                               unsigned idx) L4_NOTHROW
00437 {
00438     return l4_debugger_query_log_typeid_u(cap, name, idx, l4_utcb());
00439 }
00440
00441 L4_INLINE l4_ret_t
00442 l4_debugger_query_log_name(l4_cap_idx_t cap, unsigned idx,
00443                            char *name, unsigned namelen,
00444                            char *shortname, unsigned shortnamelen) L4_NOTHROW
00445 {
00446     return l4_debugger_query_log_name_u(cap, idx, name, namelen,
00447                                         shortname, shortnamelen, l4_utcb());
00448 }
00449
00450 L4_INLINE l4_msgtag_t
00451 l4_debugger_switch_log(l4_cap_idx_t cap, const char *name,
00452                        int on_off) L4_NOTHROW
00453 {
00454     return l4_debugger_switch_log_u(cap, name, on_off, l4_utcb());
00455 }
00456
00457 L4_INLINE l4_msgtag_t
00458 l4_debugger_query_object_name(l4_cap_idx_t cap, unsigned id,
00459                               char *name, unsigned size) L4_NOTHROW
00460 {
00461     return l4_debugger_query_object_name_u(cap, id, name, size, l4_utcb());
00462 }
00463
00464 L4_INLINE l4_msgtag_t
00465 l4_debugger_get_object_name(l4_cap_idx_t cap,
00466                             char *name, unsigned size) L4_NOTHROW
00467 {
00468     return l4_debugger_get_object_name_u(cap, name, size, l4_utcb());
00469 }
00470
00471 L4_INLINE l4_msgtag_t
00472 l4_debugger_add_image_info(l4_cap_idx_t cap, l4_addr_t base,
00473                            const char *name) L4_NOTHROW
00474 {
00475     return l4_debugger_add_image_info_u(cap, base, name, l4_utcb());
00476 }

```

## 16.495 l4/sys/err.h File Reference


Error codes.

```


#include <l4/sys/compiler.h>
#include <l4/sys/types.h>

```

Include dependency graph for `err.h`:



This graph shows which files directly or indirectly include this file:



## Enumerations

- enum `l4_error_code_t` {  
`L4_EOK` = 0 , `L4_EPERM` = 1 , `L4_ENOENT` = 2 , `L4_EIO` = 5 ,  
`L4_ENXIO` = 6 , `L4_E2BIG` = 7 , `L4_EAGAIN` = 11 , `L4_ENOMEM` = 12 ,  
`L4_EACCESS` = 13 , `L4_EFAULT` = 14 , `L4_EBUSY` = 16 , `L4_EEXIST` = 17 ,  
`L4_ENODEV` = 19 , `L4_ENOTDIR` = 20 , `L4_EINVAL` = 22 , `L4_ENOSPC` = 28 ,  
`L4_ERANGE` = 34 , `L4_ENAMETOOLONG` = 36 , `L4_ENOSYS` = 38 , `L4_EBADPROTO` = 39 ,  
`L4_EADDRNOTAVAIL` = 99 , `L4_ERRNOMAX` = 100 , `L4_ENOREPLY` = 1000 , `L4_MSGTOOSHORT` =  
1001 ,  
`L4_MSGTOOLONG` = 1002 , `L4_MSGMISSARG` = 1003 , `L4_MSGERRRANGE` = 1004 , `L4_EIPC_LO` =  
2000 ,  
`L4_EIPC_HI` = 2000 + 0x1f }  
*L4 error codes.*

## 16.495.1 Detailed Description

Error codes.

Definition in file `err.h`.

## 16.496 err.h

[Go to the documentation of this file.](#)

```

00001
00005 /*
00006  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00007  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00008  *      economic rights: Technische Universität Dresden (Germany)
00009  *
00010  * License: see LICENSE.spdx (in this directory or the directories above)
00011  */
00012 #pragma once
00013
00014 #include <l4/sys/compiler.h>
00015 #include <l4/sys/types.h>
00016
00024
00031 enum l4_error_code_t
00032 {
00033     L4_EOK                = 0,
00034     L4_EPERM              = 1,
00035     L4_ENOENT             = 2,
00036     L4_EIO                = 5,
00037     L4_ENXIO              = 6,
00038     L4_E2BIG              = 7,
00039     L4_EAGAIN             = 11,
00040     L4_ENOMEM             = 12,
00041     L4_EACCESS            = 13,
00042     L4_EFAULT             = 14,
00043     L4_EBUSY              = 16,
00044     L4_EEXIST             = 17,
00045     L4_ENODEV             = 19,
00046     L4_ENOTDIR            = 20,
00047     L4_EINVAL            = 22,
00048     L4_ENOSPC            = 28,
00049     L4_ERANGE             = 34,
00050     L4_ENAMETOOLONG       = 36,
00051     L4_ENOSYS            = 38,
00052     L4_EBADPROTO          = 39,
00053     L4_EADDRNOTAVAIL      = 99,
00054     L4_ERRNOMAX           = 100,
00055
00056     L4_ENOREPLY           = 1000,
00057     L4_EMMSGTOOSHORT      = 1001,
00058     L4_EMMSGTOOLONG       = 1002,
00059     L4_EMMSGMISSARG       = 1003,
00060     L4_EMMSGERRRANGE      = 1004,
00061
00062     L4_EIPC_LO            = 2000,
00063     L4_EIPC_HI            = 2000 + 0x1f,
00064 };
00065
00066 L4_BEGIN_DECLS
00067 L4_CV char const *l4sys_errtostr(long err) L4_NOTHROW;
00068 L4_END_DECLS
00069
00070

```

## 16.497 l4/sys/exception File Reference


Exception C++ interface.

```

#include <l4/sys/capability>
#include <l4/sys/types.h>
#include <l4/sys/cxx/ipc_types>
#include <l4/sys/cxx/ipc_iface>

```

Include dependency graph for exception:



## Data Structures

- class [L4::Exception](#)  
*Exception interface.*

## Namespaces

- namespace [L4](#)  
*L4 low-level kernel interface.*


### 16.497.1 Detailed Description

Exception C++ interface.

Definition in file [exception](#).



This graph shows which files directly or indirectly include this file:



## Data Structures

- class [L4::Factory](#)  
C++ Factory interface, see [Factory](#) for the C interface.
- struct [L4::Factory::Nil](#)  
Special type to add a void argument into the factory create stream.
- struct [L4::Factory::Lstr](#)  
Special type to add a pascal string into the factory create stream.
- class [L4::Factory::S](#)  
Stream class for the [create\(\)](#) argument stream.

## Namespaces

- namespace [L4](#)  
[L4](#) low-level kernel interface.

## 16.499.1 Detailed Description

Common factory related definitions.

Definition in file [factory](#).

## 16.500 factory

[Go to the documentation of this file.](#)

```
00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00006 /*
00007  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00008  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00009  *      economic rights: Technische Universität Dresden (Germany)
00010  *
00011  * License: see LICENSE.spdx (in this directory or the directories above)
00012  */
00013
00014 #pragma once
00015
00016 #include <l4/sys/factory.h>
00017 #include <l4/sys/capability>
00018 #include <l4/sys/snd_destination>
00019 #include <l4/sys/cxx/ipc_iface>
```

```

00020 #include <l4/sys/cxx/ipc_varg>
00021
00022 namespace L4 {
00023
00038 class Factory : public Kobject_t<Factory, Kobject, L4_PROTO_FACTORY>
00039 {
00040 public:
00041
00042     typedef l4_mword_t Proto;
00043
00047     struct Nil {};
00048
00054     struct Lstr
00055     {
00059         char const *s;
00060
00064         unsigned len;
00065
00070         Lstr(char const *s, unsigned len) noexcept : s(s), len(len) {}
00071     };
00072
00079     class S
00080     {
00081     private:
00082         l4_utcb_t *u;
00083         l4_msgtag_t t;
00084         l4_cap_idx_t f;
00085
00086         template<typename T>
00087         static T &&move(T &c) { return static_cast<T &&>(c); }
00088
00089     public:
00090         S(S const &) = delete;
00091         S &operator = (S const &) &= delete;
00092
00098         S(S &&o) noexcept
00099         : u(o.u), t(o.t), f(o.f)
00100         { o.t.raw = 0; }
00101
00102         S &operator = (S &&o) & noexcept
00103         {
00104             u = o.u;
00105             t = o.t;
00106             f = o.f;
00107             o.t.raw = 0;
00108             return *this;
00109         }
00110
00125         S(l4_cap_idx_t f, long obj, L4::Cap<void> target,
00126           l4_utcb_t *utcb) noexcept
00127         : u(utcb), t(l4_factory_create_start_u(obj, target.cap(), u)), f(f)
00128         {}
00129
00139         ~S() noexcept
00140         {
00141             if (t.raw)
00142                 l4_factory_create_commit_u(f, t, u);
00143         }
00144
00157         operator l4_msgtag_t () noexcept
00158         {
00159             l4_msgtag_t r = l4_factory_create_commit_u(f, t, u);
00160             t.raw = 0;
00161             return r;
00162         }
00163
00169         void put(l4_mword_t i) noexcept
00170         {
00171             l4_factory_create_add_int_u(i, &t, u);
00172         }
00173
00179         void put(l4_umword_t i) noexcept
00180         {
00181             l4_factory_create_add_uint_u(i, &t, u);
00182         }
00183
00191         void put(char const *s) & noexcept
00192         {
00193             l4_factory_create_add_str_u(s, &t, u);
00194         }
00195
00205         void put(Lstr const &s) & noexcept
00206         {
00207             l4_factory_create_add_lstr_u(s.s, s.len, &t, u);
00208         }
00209
00213         void put(Nil) & noexcept

```

```

00214     {
00215         l4_factory_create_add_nil_u(&t, u);
00216     }
00217
00223     void put(l4_fpage_t d) & noexcept
00224     {
00225         l4_factory_create_add_fpage_u(d, &t, u);
00226     }
00227
00236     template<typename T>
00237     S &operator « (T const &d) & noexcept
00238     {
00239         put(d);
00240         return *this;
00241     }
00242
00251     template<typename T>
00252     S &&operator « (T const &d) && noexcept
00253     {
00254         put(d);
00255         return _move(*this);
00256     }
00257 };
00258
00259 public:
00261
00292     S create(Cap<void> target, long obj, l4_utcb_t *utcb = l4_utcb()) noexcept
00293     {
00294         return S(cap(), obj, target, utcb);
00295     }
00296
00328     template<typename OBJ>
00329     S create(Cap<OBJ> target, l4_utcb_t *utcb = l4_utcb()) noexcept
00330     {
00331         return S(cap(), OBJ::Protocol, target, utcb);
00332     }
00333
00334     L4_INLINE_RPC_NF(
00335         l4_msgtag_t, create, (L4::Ipc::Out<L4::Cap<void> > target, l4_mword_t obj,
00336                             L4::Ipc::Varg const *args),
00337         L4::Ipc::Call_t<L4_CAP_FPAGE_S>);
00338
00370     l4_msgtag_t create_task(Cap<Task> const &target_cap,
00371                             l4_fpage_t *utcb_area,
00372                             l4_utcb_t *utcb = l4_utcb()) noexcept
00373     { return l4_factory_create_task_u(cap(), target_cap.cap(), utcb_area, utcb); }
00374
00404     l4_msgtag_t create_factory(Cap<Factory> const &target_cap,
00405                                unsigned long limit,
00406                                l4_utcb_t *utcb = l4_utcb()) noexcept
00407     { return l4_factory_create_factory_u(cap(), target_cap.cap(), limit, utcb); }
00408
00440     l4_msgtag_t create_gate(Cap<void> const &target_cap,
00441                             Cap<Snd_destination> const &snd_dst_cap,
00442                             l4_umword_t label,
00443                             l4_utcb_t *utcb = l4_utcb()) noexcept
00444     {
00445         return l4_factory_create_gate_u(cap(), target_cap.cap(), snd_dst_cap.cap(),
00446                                         label, utcb);
00447     }
00448
00475     l4_msgtag_t create_thread_group(Cap<Thread_group> const &target_cap,
00476                                     unsigned policy,
00477                                     l4_utcb_t *utcb = l4_utcb()) noexcept
00478     {
00479         return l4_factory_create_thread_group_u(cap(), target_cap.cap(),
00480                                                 policy, utcb);
00481     }
00482
00483     typedef L4::Typeid::Rpc_nocode<create_t> Rpcs;
00484 };
00485
00486 }

```

## 16.501 l4/sys/factory.h File Reference

Common factory related definitions.


```

#include <l4/sys/compiler.h>
#include <l4/sys/types.h>


```



```
#include <l4/sys/utcb.h>
#include <l4/sys/ipc.h>
Include dependency graph for factory.h:
```



This graph shows which files directly or indirectly include this file:



## Functions

- [l4\\_msgtag\\_t l4\\_factory\\_create\\_task](#) ([l4\\_cap\\_idx\\_t](#) factory, [l4\\_cap\\_idx\\_t](#) target\_cap, [l4\\_fpage\\_t](#) \*utcb\_area) [L4\\_NOTHROW](#)  
Create a new task.
- [l4\\_msgtag\\_t l4\\_factory\\_create\\_thread](#) ([l4\\_cap\\_idx\\_t](#) factory, [l4\\_cap\\_idx\\_t](#) target\_cap) [L4\\_NOTHROW](#)  
Create a new thread.
- [l4\\_msgtag\\_t l4\\_factory\\_create\\_factory](#) ([l4\\_cap\\_idx\\_t](#) factory, [l4\\_cap\\_idx\\_t](#) target\_cap, unsigned long limit) [L4\\_NOTHROW](#)  
Create a new factory.
- [l4\\_msgtag\\_t l4\\_factory\\_create\\_gate](#) ([l4\\_cap\\_idx\\_t](#) factory, [l4\\_cap\\_idx\\_t](#) target\_cap, [l4\\_cap\\_idx\\_t](#) snd\_dst\_↔ cap, [l4\\_umword\\_t](#) label) [L4\\_NOTHROW](#)  
Create a new IPC gate, optionally bound to a send destination (a thread or thread group).

- [l4\\_msgtag\\_t l4\\_factory\\_create\\_irq](#) ([l4\\_cap\\_idx\\_t](#) factory, [l4\\_cap\\_idx\\_t](#) target\_cap) [L4\\_NOTHROW](#)  
*Create a new IRQ sender.*
- [l4\\_msgtag\\_t l4\\_factory\\_create\\_vm](#) ([l4\\_cap\\_idx\\_t](#) factory, [l4\\_cap\\_idx\\_t](#) target\_cap) [L4\\_NOTHROW](#)  
*Create a new virtual machine.*
- [l4\\_msgtag\\_t l4\\_factory\\_create\\_vcpu\\_context](#) ([l4\\_cap\\_idx\\_t](#) factory, [l4\\_cap\\_idx\\_t](#) target\_cap) [L4\\_NOTHROW](#)  
*Create a new vCPU context.*
- [l4\\_msgtag\\_t l4\\_factory\\_create\\_thread\\_group](#) ([l4\\_cap\\_idx\\_t](#) factory, [l4\\_cap\\_idx\\_t](#) target\_cap, unsigned policy) [L4\\_NOTHROW](#)  
*Create a new thread group.*
- [l4\\_msgtag\\_t l4\\_factory\\_create](#) ([l4\\_cap\\_idx\\_t](#) factory, long obj, [l4\\_cap\\_idx\\_t](#) target) [L4\\_NOTHROW](#)  
*Create a new object.*

## 16.501.1 Detailed Description

Common factory related definitions.

Definition in file [factory.h](#).

## 16.502 factory.h

[Go to the documentation of this file.](#)

```

00001
00006 /*
00007  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00008  *      Alexander Warg <warg@os.inf.tu-dresden.de>,
00009  *      Björn Döbel <doebel@os.inf.tu-dresden.de>,
00010  *      Torsten Frenzel <frenzel@os.inf.tu-dresden.de>,
00011  *      Henning Schild <hschild@os.inf.tu-dresden.de>
00012  *      economic rights: Technische Universität Dresden (Germany)
00013  *
00014  * License: see LICENSE.spdx (in this directory or the directories above)
00015  */
00016 #pragma once
00017
00018 #include <l4/sys/compiler.h>
00019 #include <l4/sys/types.h>
00020 #include <l4/sys/utcb.h>
00021
00050
00056
00086 L4_INLINE l4_msgtag_t
00087 l4_factory_create_task(l4_cap_idx_t factory, l4_cap_idx_t target_cap,
00088                      l4_fpage_t *utcb_area) L4_NOTHROW;
00089
00094 L4_INLINE l4_msgtag_t
00095 l4_factory_create_task_u(l4_cap_idx_t factory, l4_cap_idx_t target_cap,
00096                        l4_fpage_t *utcb_area, l4_utcb_t *utcb) L4_NOTHROW;
00097
00116 L4_INLINE l4_msgtag_t
00117 l4_factory_create_thread(l4_cap_idx_t factory,
00118                        l4_cap_idx_t target_cap) L4_NOTHROW;
00119
00124 L4_INLINE l4_msgtag_t
00125 l4_factory_create_thread_u(l4_cap_idx_t factory,
00126                          l4_cap_idx_t target_cap, l4_utcb_t *utcb) L4_NOTHROW;
00127
00153 L4_INLINE l4_msgtag_t
00154 l4_factory_create_factory(l4_cap_idx_t factory, l4_cap_idx_t target_cap,
00155                          unsigned long limit) L4_NOTHROW;
00156
00161 L4_INLINE l4_msgtag_t
00162 l4_factory_create_factory_u(l4_cap_idx_t factory, l4_cap_idx_t target_cap,
00163                           unsigned long limit, l4_utcb_t *utcb) L4_NOTHROW;
00164
00194 L4_INLINE l4_msgtag_t
00195 l4_factory_create_gate(l4_cap_idx_t factory,
00196                      l4_cap_idx_t target_cap,
00197                      l4_cap_idx_t snd_dst_cap, l4_umword_t label) L4_NOTHROW;

```

```

00198
00203 L4_INLINE l4_msgtag_t
00204 l4_factory_create_gate_u(l4_cap_idx_t factory,
00205                          l4_cap_idx_t target_cap,
00206                          l4_cap_idx_t snd_dst_cap, l4_umword_t label,
00207                          l4_utcb_t *utcb) L4_NOTHROW;
00208
00225 L4_INLINE l4_msgtag_t
00226 l4_factory_create_irq(l4_cap_idx_t factory,
00227                      l4_cap_idx_t target_cap) L4_NOTHROW;
00228
00233 L4_INLINE l4_msgtag_t
00234 l4_factory_create_irq_u(l4_cap_idx_t factory,
00235                        l4_cap_idx_t target_cap, l4_utcb_t *utcb) L4_NOTHROW;
00236
00255 L4_INLINE l4_msgtag_t
00256 l4_factory_create_vm(l4_cap_idx_t factory,
00257                    l4_cap_idx_t target_cap) L4_NOTHROW;
00258
00278 L4_INLINE l4_msgtag_t
00279 l4_factory_create_vcpu_context(l4_cap_idx_t factory,
00280                              l4_cap_idx_t target_cap) L4_NOTHROW;
00281
00309 L4_INLINE l4_msgtag_t
00310 l4_factory_create_thread_group(l4_cap_idx_t factory,
00311                               l4_cap_idx_t target_cap,
00312                               unsigned policy) L4_NOTHROW;
00313
00318 L4_INLINE l4_msgtag_t
00319 l4_factory_create_vm_u(l4_cap_idx_t factory,
00320                      l4_cap_idx_t target_cap, l4_utcb_t *utcb) L4_NOTHROW;
00321
00326 L4_INLINE l4_msgtag_t
00327 l4_factory_create_vcpu_context_u(l4_cap_idx_t factory,
00328                                  l4_cap_idx_t target_cap,
00329                                  l4_utcb_t *utcb) L4_NOTHROW;
00330
00335 L4_INLINE l4_msgtag_t
00336 l4_factory_create_thread_group_u(l4_cap_idx_t factory,
00337                                  l4_cap_idx_t target_cap,
00338                                  unsigned policy,
00339                                  l4_utcb_t *u) L4_NOTHROW;
00340
00345 L4_INLINE l4_msgtag_t
00346 l4_factory_create_start_u(long obj, l4_cap_idx_t target,
00347                          l4_utcb_t *utcb) L4_NOTHROW;
00348
00353 L4_INLINE int
00354 l4_factory_create_add_fpage_u(l4_fpage_t d, l4_msgtag_t *tag,
00355                              l4_utcb_t *utcb) L4_NOTHROW;
00356
00361 L4_INLINE int
00362 l4_factory_create_add_int_u(l4_mword_t d, l4_msgtag_t *tag,
00363                           l4_utcb_t *utcb) L4_NOTHROW;
00364
00369 L4_INLINE int
00370 l4_factory_create_add_uint_u(l4_umword_t d, l4_msgtag_t *tag,
00371                             l4_utcb_t *utcb) L4_NOTHROW;
00372
00377 L4_INLINE int
00378 l4_factory_create_add_str_u(char const *s, l4_msgtag_t *tag,
00379                            l4_utcb_t *utcb) L4_NOTHROW;
00380
00385 L4_INLINE int
00386 l4_factory_create_add_lstr_u(char const *s, unsigned len, l4_msgtag_t *tag,
00387                             l4_utcb_t *utcb) L4_NOTHROW;
00388
00393 L4_INLINE int
00394 l4_factory_create_add_nil_u(l4_msgtag_t *tag, l4_utcb_t *utcb) L4_NOTHROW;
00395
00400 L4_INLINE l4_msgtag_t
00401 l4_factory_create_commit_u(l4_cap_idx_t factory, l4_msgtag_t tag,
00402                          l4_utcb_t *utcb) L4_NOTHROW;
00403
00408 L4_INLINE l4_msgtag_t
00409 l4_factory_create_u(l4_cap_idx_t factory, long obj, l4_cap_idx_t target,
00410                   l4_utcb_t *utcb) L4_NOTHROW;
00411
00412
00430 L4_INLINE l4_msgtag_t
00431 l4_factory_create(l4_cap_idx_t factory, long obj,
00432                 l4_cap_idx_t target) L4_NOTHROW;
00433
00434 /* IMPLEMENTATION -----*/
00435
00436 #include <l4/sys/ipc.h>
00437

```

```

00438 L4_INLINE l4_msgtag_t
00439 l4_factory_create_task_u(l4_cap_idx_t factory,
00440                          l4_cap_idx_t target_cap, l4_fpage_t *utcb_area,
00441                          l4_utcb_t *u) L4_NOTHROW
00442 {
00443     l4_msgtag_t t;
00444     t = l4_factory_create_start_u(L4_PROTO_TASK, target_cap, u);
00445     l4_factory_create_add_fpage_u(*utcb_area, &t, u);
00446     t = l4_factory_create_commit_u(factory, t, u);
00447     if (!l4_msgtag_has_error(t))
00448     {
00449         l4_msg_regs_t *v = l4_utcb_mr_u(u);
00450         utcb_area->raw = v->mr[0];
00451     }
00452     return t;
00453 }
00454
00455 L4_INLINE l4_msgtag_t
00456 l4_factory_create_thread_u(l4_cap_idx_t factory,
00457                           l4_cap_idx_t target_cap, l4_utcb_t *u) L4_NOTHROW
00458 {
00459     return l4_factory_create_u(factory, L4_PROTO_THREAD, target_cap, u);
00460 }
00461
00462 L4_INLINE l4_msgtag_t
00463 l4_factory_create_factory_u(l4_cap_idx_t factory,
00464                             l4_cap_idx_t target_cap, unsigned long limit,
00465                             l4_utcb_t *u) L4_NOTHROW
00466 {
00467     l4_msgtag_t t;
00468     t = l4_factory_create_start_u(L4_PROTO_FACTORY, target_cap, u);
00469     l4_factory_create_add_uint_u(limit, &t, u);
00470     return l4_factory_create_commit_u(factory, t, u);
00471 }
00472
00473 L4_INLINE l4_msgtag_t
00474 l4_factory_create_gate_u(l4_cap_idx_t factory,
00475                          l4_cap_idx_t target_cap,
00476                          l4_cap_idx_t snd_dst_cap, l4_umword_t label,
00477                          l4_utcb_t *u) L4_NOTHROW
00478 {
00479     l4_msgtag_t t;
00480     l4_msg_regs_t *v;
00481     int items = 0;
00482     t = l4_factory_create_start_u(0, target_cap, u);
00483     l4_factory_create_add_uint_u(label, &t, u);
00484     v = l4_utcb_mr_u(u);
00485     if (!(snd_dst_cap & L4_INVALID_CAP_BIT))
00486     {
00487         items = 1;
00488         v->mr[3] = l4_map_obj_control(0,0);
00489         v->mr[4] = l4_obj_fpage(snd_dst_cap, 0, L4_CAP_FPAGE_RWS).raw;
00490     }
00491     t = l4_msgtag(l4_msgtag_label(t), l4_msgtag_words(t), items, l4_msgtag_flags(t));
00492     return l4_factory_create_commit_u(factory, t, u);
00493 }
00494
00495 L4_INLINE l4_msgtag_t
00496 l4_factory_create_irq_u(l4_cap_idx_t factory,
00497                         l4_cap_idx_t target_cap, l4_utcb_t *u) L4_NOTHROW
00498 {
00499     return l4_factory_create_u(factory, L4_PROTO_IRQ_SENDER, target_cap, u);
00500 }
00501
00502 L4_INLINE l4_msgtag_t
00503 l4_factory_create_vm_u(l4_cap_idx_t factory,
00504                       l4_cap_idx_t target_cap,
00505                       l4_utcb_t *u) L4_NOTHROW
00506 {
00507     return l4_factory_create_u(factory, L4_PROTO_VM, target_cap, u);
00508 }
00509
00510 L4_INLINE l4_msgtag_t
00511 l4_factory_create_vcpu_context_u(l4_cap_idx_t factory,
00512                                  l4_cap_idx_t target_cap,
00513                                  l4_utcb_t *u) L4_NOTHROW
00514 {
00515     return l4_factory_create_u(factory, L4_PROTO_VCPU_CONTEXT, target_cap, u);
00516 }
00517
00518 L4_INLINE l4_msgtag_t
00519 l4_factory_create_thread_group_u(l4_cap_idx_t factory,
00520                                  l4_cap_idx_t target_cap,
00521                                  unsigned policy,
00522                                  l4_utcb_t *u) L4_NOTHROW
00523 {
00524     l4_msgtag_t t = l4_factory_create_start_u(L4_PROTO_THREAD_GROUP, target_cap, u);

```

```

00525     l4_factory_create_add_uint_u(policy, &t, u);
00526     return l4_factory_create_commit_u(factory, t, u);
00527 }
00528
00529
00530 L4_INLINE l4_msgtag_t
00531 l4_factory_create_task(l4_cap_idx_t factory,
00532                       l4_cap_idx_t target_cap, l4_fpage_t *utcb_area) L4_NOTHROW
00533 {
00534     return l4_factory_create_task_u(factory, target_cap, utcb_area, l4_utcb());
00535 }
00536
00537 L4_INLINE l4_msgtag_t
00538 l4_factory_create_thread(l4_cap_idx_t factory,
00539                          l4_cap_idx_t target_cap) L4_NOTHROW
00540 {
00541     return l4_factory_create_thread_u(factory, target_cap, l4_utcb());
00542 }
00543
00544 L4_INLINE l4_msgtag_t
00545 l4_factory_create_factory(l4_cap_idx_t factory,
00546                           l4_cap_idx_t target_cap, unsigned long limit) L4_NOTHROW
00547 {
00548     return l4_factory_create_factory_u(factory, target_cap, limit, l4_utcb());
00549 }
00550
00551
00552 L4_INLINE l4_msgtag_t
00553 l4_factory_create_gate(l4_cap_idx_t factory,
00554                        l4_cap_idx_t target_cap,
00555                        l4_cap_idx_t snd_dst_cap, l4_umword_t label) L4_NOTHROW
00556 {
00557     return l4_factory_create_gate_u(factory, target_cap, snd_dst_cap, label, l4_utcb());
00558 }
00559
00560 L4_INLINE l4_msgtag_t
00561 l4_factory_create_irq(l4_cap_idx_t factory,
00562                       l4_cap_idx_t target_cap) L4_NOTHROW
00563 {
00564     return l4_factory_create_irq_u(factory, target_cap, l4_utcb());
00565 }
00566
00567 L4_INLINE l4_msgtag_t
00568 l4_factory_create_vm(l4_cap_idx_t factory,
00569                      l4_cap_idx_t target_cap) L4_NOTHROW
00570 {
00571     return l4_factory_create_vm_u(factory, target_cap, l4_utcb());
00572 }
00573
00574 L4_INLINE l4_msgtag_t
00575 l4_factory_create_vcpu_context(l4_cap_idx_t factory,
00576                                l4_cap_idx_t target_cap) L4_NOTHROW
00577 {
00578     return l4_factory_create_vcpu_context_u(factory, target_cap, l4_utcb());
00579 }
00580
00581 L4_INLINE l4_msgtag_t
00582 l4_factory_create_thread_group(l4_cap_idx_t factory,
00583                                l4_cap_idx_t target_cap,
00584                                unsigned policy) L4_NOTHROW
00585 {
00586     return l4_factory_create_thread_group_u(factory, target_cap, policy, l4_utcb());
00587 }
00588
00589
00590 L4_INLINE l4_msgtag_t
00591 l4_factory_create_start_u(long obj, l4_cap_idx_t target_cap,
00592                           l4_utcb_t *u) L4_NOTHROW
00593 {
00594     l4_msg_regs_t *v = l4_utcb_mr_u(u);
00595     l4_buf_regs_t *b = l4_utcb_br_u(u);
00596     v->mr[0] = obj;
00597     b->bdr = 0;
00598     b->br[0] = target_cap | L4_RCV_ITEM_SINGLE_CAP;
00599     return l4_msgtag(L4_PROTO_FACTORY, 1, 0, 0);
00600 }
00601
00602 L4_INLINE int
00603 l4_factory_create_add_fpage_u(l4_fpage_t d, l4_msgtag_t *tag,
00604                               l4_utcb_t *u) L4_NOTHROW
00605 {
00606     l4_msg_regs_t *v = l4_utcb_mr_u(u);
00607     int w = l4_msgtag_words(*tag);
00608     if (w + 2 > L4_UTCB_GENERIC_DATA_SIZE)
00609         return 0;
00610     v->mr[w] = L4_VARG_TYPE_FPAGE | (sizeof(l4_fpage_t) << 16);
00611     v->mr[w + 1] = d.raw;

```


```

00612     w += 2;
00613     tag->raw = (tag->raw & ~0x3fUL) | (w & 0x3f);
00614     return 1;
00615 }
00616
00617 L4_INLINE int
00618 l4_factory_create_add_int_u(l4_mword_t d, l4_msgtag_t *tag,
00619                             l4_utcb_t *u) L4_NOTHROW
00620 {
00621     l4_msg_regs_t *v = l4_utcb_mr_u(u);
00622     int w = l4_msgtag_words(*tag);
00623     if (w + 2 > L4_UTCB_GENERIC_DATA_SIZE)
00624         return 0;
00625     v->mr[w] = L4_VARG_TYPE_MWORD | (sizeof(l4_mword_t) << 16);
00626     v->mr[w + 1] = d;
00627     w += 2;
00628     tag->raw = (tag->raw & ~0x3fUL) | (w & 0x3f);
00629     return 1;
00630 }
00631
00632 L4_INLINE int
00633 l4_factory_create_add_uint_u(l4_umword_t d, l4_msgtag_t *tag,
00634                              l4_utcb_t *u) L4_NOTHROW
00635 {
00636     l4_msg_regs_t *v = l4_utcb_mr_u(u);
00637     int w = l4_msgtag_words(*tag);
00638     if (w + 2 > L4_UTCB_GENERIC_DATA_SIZE)
00639         return 0;
00640     v->mr[w] = L4_VARG_TYPE_UMWORD | (sizeof(l4_umword_t) << 16);
00641     v->mr[w + 1] = d;
00642     w += 2;
00643     tag->raw = (tag->raw & ~0x3fUL) | (w & 0x3f);
00644     return 1;
00645 }
00646
00647 L4_INLINE int
00648 l4_factory_create_add_str_u(char const *s, l4_msgtag_t *tag,
00649                             l4_utcb_t *u) L4_NOTHROW
00650 {
00651     return l4_factory_create_add_lstr_u(s, __builtin_strlen(s) + 1, tag, u);
00652 }
00653
00654 L4_INLINE int
00655 l4_factory_create_add_lstr_u(char const *s, unsigned len, l4_msgtag_t *tag,
00656                              l4_utcb_t *u) L4_NOTHROW
00657 {
00658     l4_msg_regs_t *v = l4_utcb_mr_u(u);
00659     unsigned w = l4_msgtag_words(*tag);
00660     char *c;
00661     unsigned i;
00662     if (w + 1 + l4_bytes_to_mwords(len) > L4_UTCB_GENERIC_DATA_SIZE)
00663         return 0;
00664     v->mr[w] = L4_VARG_TYPE_STRING | (len << 16);
00665     c = (char*)&v->mr[w + 1];
00666     for (i = 0; i < len; ++i)
00667         *c++ = *s++;
00668     w = w + 1 + l4_bytes_to_mwords(len);
00669     tag->raw = (tag->raw & ~0x3fUL) | (w & 0x3f);
00670     return 1;
00671 }
00672
00673 L4_INLINE int
00674 l4_factory_create_add_nil_u(l4_msgtag_t *tag, l4_utcb_t *utcb) L4_NOTHROW
00675 {
00676     l4_msg_regs_t *v = l4_utcb_mr_u(utcb);
00677     int w = l4_msgtag_words(*tag);
00678     v->mr[w] = L4_VARG_TYPE_NIL;
00679     ++w;
00680     tag->raw = (tag->raw & ~0x3fUL) | (w & 0x3f);
00681     return 1;
00682 }
00683
00684 L4_INLINE l4_msgtag_t
00685 l4_factory_create_commit_u(l4_cap_idx_t factory, l4_msgtag_t tag,
00686                             l4_utcb_t *u) L4_NOTHROW
00687 {
00688     return l4_ipc_call(factory, u, tag, L4_IPC_NEVER);
00689 }
00690
00691 L4_INLINE l4_msgtag_t
00692 l4_factory_create_u(l4_cap_idx_t factory, long obj, l4_cap_idx_t target,

```

## 16.503 I4/sys/icu File Reference

```
#include <linux/sys/irq>
```



### 16.503.1 Detailed Description

Interrupt controller.

Definition in file [icu](#).

## 16.504 icu

[Go to the documentation of this file.](#)

```
00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00007 /*
00008  * (c) 2008-2009 Alexander Warg <warg@os.inf.tu-dresden.de>
00009  *     economic rights: Technische Universität Dresden (Germany)
00010  *
00011  * License: see LICENSE.spdx (in this directory or the directories above)
00012  */
00013 #pragma once
00014
00015 #include <l4/sys/irq>
```


## 16.505 l4/sys/icu.h File Reference

Interrupt controller.

```
#include <l4/sys/kernel_object.h>
```


```
#include <l4/sys/ipc.h>
```

Include dependency graph for icu.h:





This graph shows which files directly or indirectly include this file:



## Data Structures

- struct [l4\\_icu\\_info\\_t](#)  
*Info structure for an ICU.*
- struct [l4\\_icu\\_msi\\_info\\_t](#)  
*Info to use for a specific MSI.*

## Typedefs

- typedef struct [l4\\_icu\\_info\\_t](#) [l4\\_icu\\_info\\_t](#)  
*Info structure for an ICU.*
- typedef struct [l4\\_icu\\_msi\\_info\\_t](#) [l4\\_icu\\_msi\\_info\\_t](#)  
*Info to use for a specific MSI.*

## Enumerations

- enum [L4\\_icu\\_flags](#) { [L4\\_ICU\\_FLAG\\_MSI](#) }  
*Flags for IRQ numbers used for the ICU.*
- enum [L4\\_irq\\_mode](#) {  
[L4\\_IRQ\\_F\\_NONE](#) = 0 , [L4\\_IRQ\\_F\\_SET\\_MODE](#) = 0x1 , [L4\\_IRQ\\_F\\_LEVEL](#) = 0x2 , [L4\\_IRQ\\_F\\_EDGE](#) = 0x0 ,  
[L4\\_IRQ\\_F\\_POS](#) = 0x0 , [L4\\_IRQ\\_F\\_NEG](#) = 0x4 , [L4\\_IRQ\\_F\\_BOTH](#) = 0x8 , [L4\\_IRQ\\_F\\_LEVEL\\_HIGH](#) =  
[L4\\_IRQ\\_F\\_SET\\_MODE](#) | [L4\\_IRQ\\_F\\_LEVEL](#) | [L4\\_IRQ\\_F\\_POS](#) ,  
[L4\\_IRQ\\_F\\_LEVEL\\_LOW](#) = [L4\\_IRQ\\_F\\_SET\\_MODE](#) | [L4\\_IRQ\\_F\\_LEVEL](#) | [L4\\_IRQ\\_F\\_NEG](#) , [L4\\_IRQ\\_F\\_POS\\_EDGE](#)  
= [L4\\_IRQ\\_F\\_SET\\_MODE](#) | [L4\\_IRQ\\_F\\_EDGE](#) | [L4\\_IRQ\\_F\\_POS](#) , [L4\\_IRQ\\_F\\_NEG\\_EDGE](#) = [L4\\_IRQ\\_F\\_](#)  
[SET\\_MODE](#) | [L4\\_IRQ\\_F\\_EDGE](#) | [L4\\_IRQ\\_F\\_NEG](#) , [L4\\_IRQ\\_F\\_BOTH\\_EDGE](#) = [L4\\_IRQ\\_F\\_SET\\_MODE](#) |  
[L4\\_IRQ\\_F\\_EDGE](#) | [L4\\_IRQ\\_F\\_BOTH](#) ,  
[L4\\_IRQ\\_F\\_MASK](#) = 0xf , [L4\\_IRQ\\_F\\_SET\\_WAKEUP](#) = 0x10 , [L4\\_IRQ\\_F\\_CLEAR\\_WAKEUP](#) = 0x20 }  
*Interrupt attributes.*
- enum [L4\\_icu\\_opcode](#) {  
[L4\\_ICU\\_OP\\_BIND](#) , [L4\\_ICU\\_OP\\_UNBIND](#) , [L4\\_ICU\\_OP\\_INFO](#) , [L4\\_ICU\\_OP\\_MSI\\_INFO](#) ,  
[L4\\_ICU\\_OP\\_UNMASK](#) , [L4\\_ICU\\_OP\\_MASK](#) , [L4\\_ICU\\_OP\\_SET\\_MODE](#) }  
*Opcodes to the ICU interface.*

## Functions

- [l4\\_msgtag\\_t l4\\_icu\\_bind](#) ([l4\\_cap\\_idx\\_t](#) icu, unsigned irqnum, [l4\\_cap\\_idx\\_t](#) irq) [L4\\_NOTHROW](#)  
*Bind an interrupt line of an interrupt controller to an interrupt object.*
- [l4\\_msgtag\\_t l4\\_icu\\_bind\\_u](#) ([l4\\_cap\\_idx\\_t](#) icu, unsigned irqnum, [l4\\_cap\\_idx\\_t](#) irq, [l4\\_utcb\\_t](#) \*utcb) [L4\\_NOTHROW](#)  
*Bind an interrupt line of an interrupt controller to an interrupt object.*
- [l4\\_msgtag\\_t l4\\_icu\\_unbind](#) ([l4\\_cap\\_idx\\_t](#) icu, unsigned irqnum, [l4\\_cap\\_idx\\_t](#) irq) [L4\\_NOTHROW](#)  
*Remove binding of an interrupt line from the interrupt controller object.*
- [l4\\_msgtag\\_t l4\\_icu\\_unbind\\_u](#) ([l4\\_cap\\_idx\\_t](#) icu, unsigned irqnum, [l4\\_cap\\_idx\\_t](#) irq, [l4\\_utcb\\_t](#) \*utcb) [L4\\_NOTHROW](#)  
*Remove binding of an interrupt line from the interrupt controller object.*
- [l4\\_msgtag\\_t l4\\_icu\\_set\\_mode](#) ([l4\\_cap\\_idx\\_t](#) icu, unsigned irqnum, [l4\\_umword\\_t](#) mode) [L4\\_NOTHROW](#)  
*Set interrupt mode.*
- [l4\\_msgtag\\_t l4\\_icu\\_set\\_mode\\_u](#) ([l4\\_cap\\_idx\\_t](#) icu, unsigned irqnum, [l4\\_umword\\_t](#) mode, [l4\\_utcb\\_t](#) \*utcb) [L4\\_NOTHROW](#)  
*Set interrupt mode.*
- [l4\\_msgtag\\_t l4\\_icu\\_info](#) ([l4\\_cap\\_idx\\_t](#) icu, [l4\\_icu\\_info\\_t](#) \*info) [L4\\_NOTHROW](#)  
*Get information about the ICU features.*
- [l4\\_msgtag\\_t l4\\_icu\\_info\\_u](#) ([l4\\_cap\\_idx\\_t](#) icu, [l4\\_icu\\_info\\_t](#) \*info, [l4\\_utcb\\_t](#) \*utcb) [L4\\_NOTHROW](#)  
*Get information about the ICU features.*
- [l4\\_msgtag\\_t l4\\_icu\\_msi\\_info](#) ([l4\\_cap\\_idx\\_t](#) icu, unsigned irqnum, [l4\\_uint64\\_t](#) source, [l4\\_icu\\_msi\\_info\\_t](#) \*msi\_info) [L4\\_NOTHROW](#)  
*Get MSI info about IRQ.*
- [l4\\_msgtag\\_t l4\\_icu\\_msi\\_info\\_u](#) ([l4\\_cap\\_idx\\_t](#) icu, unsigned irqnum, [l4\\_uint64\\_t](#) source, [l4\\_icu\\_msi\\_info\\_t](#) \*msi\_info, [l4\\_utcb\\_t](#) \*utcb) [L4\\_NOTHROW](#)  
*Get MSI info about IRQ.*
- [l4\\_msgtag\\_t l4\\_icu\\_unmask](#) ([l4\\_cap\\_idx\\_t](#) icu, unsigned irqnum, [l4\\_umword\\_t](#) \*label, [l4\\_timeout\\_t](#) to) [L4\\_NOTHROW](#)  
*Unmask an IRQ line.*
- [l4\\_msgtag\\_t l4\\_icu\\_unmask\\_u](#) ([l4\\_cap\\_idx\\_t](#) icu, unsigned irqnum, [l4\\_umword\\_t](#) \*label, [l4\\_timeout\\_t](#) to, [l4\\_utcb\\_t](#) \*utcb) [L4\\_NOTHROW](#)  
*Unmask the given interrupt line.*
- [l4\\_msgtag\\_t l4\\_icu\\_mask](#) ([l4\\_cap\\_idx\\_t](#) icu, unsigned irqnum, [l4\\_umword\\_t](#) \*label, [l4\\_timeout\\_t](#) to) [L4\\_NOTHROW](#)  
*Mask an IRQ line.*
- [l4\\_msgtag\\_t l4\\_icu\\_mask\\_u](#) ([l4\\_cap\\_idx\\_t](#) icu, unsigned irqnum, [l4\\_umword\\_t](#) \*label, [l4\\_timeout\\_t](#) to, [l4\\_utcb\\_t](#) \*utcb) [L4\\_NOTHROW](#)  
*Mask an IRQ line.*

### 16.505.1 Detailed Description

Interrupt controller.

Definition in file [icu.h](#).

## 16.506 icu.h

[Go to the documentation of this file.](#)

```

00001
00006 /*
00007  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00008  *      Alexander Warg <warg@os.inf.tu-dresden.de>,
00009  *      Torsten Frenzel <frenzel@os.inf.tu-dresden.de>
00010  *      economic rights: Technische Universität Dresden (Germany)
00011  *
00012  * License: see LICENSE.spdx (in this directory or the directories above)
00013  */
00014 #pragma once
00015
00016 #include <l4/sys/kernel_object.h>
00017 #include <l4/sys/ipc.h>
00018
00047
00048
00053 enum L4_icu_flags
00054 {
00062     L4_ICU_FLAG_MSI = 0x80000000,
00063 };
00064
00065
00070 enum L4_irq_mode
00071 {
00073     L4_IRQ_F_NONE           = 0,
00074     L4_IRQ_F_SET_MODE      = 0x1,
00075     L4_IRQ_F_LEVEL         = 0x2,
00076     L4_IRQ_F_EDGE         = 0x0,
00077     L4_IRQ_F_POS           = 0x0,
00078     L4_IRQ_F_NEG           = 0x4,
00079     L4_IRQ_F_BOTH          = 0x8,
00080     L4_IRQ_F_LEVEL_HIGH    = L4_IRQ_F_SET_MODE | L4_IRQ_F_LEVEL | L4_IRQ_F_POS,
00081     L4_IRQ_F_LEVEL_LOW     = L4_IRQ_F_SET_MODE | L4_IRQ_F_LEVEL | L4_IRQ_F_NEG,
00082     L4_IRQ_F_POS_EDGE      = L4_IRQ_F_SET_MODE | L4_IRQ_F_EDGE | L4_IRQ_F_POS,
00083     L4_IRQ_F_NEG_EDGE      = L4_IRQ_F_SET_MODE | L4_IRQ_F_EDGE | L4_IRQ_F_NEG,
00084     L4_IRQ_F_BOTH_EDGE     = L4_IRQ_F_SET_MODE | L4_IRQ_F_EDGE | L4_IRQ_F_BOTH,
00085     L4_IRQ_F_MASK          = 0xf,
00086
00088     L4_IRQ_F_SET_WAKEUP    = 0x10,
00089     L4_IRQ_F_CLEAR_WAKEUP  = 0x20,
00090 };
00091
00092
00097 enum L4_icu_opcode
00098 {
00104     L4_ICU_OP_BIND = 0,
00105
00111     L4_ICU_OP_UNBIND = 1,
00112
00118     L4_ICU_OP_INFO = 2,
00119
00125     L4_ICU_OP_MSI_INFO = 3,
00126
00132     L4_ICU_OP_UNMASK = 4,
00133
00139     L4_ICU_OP_MASK = 5,
00140
00146     L4_ICU_OP_SET_MODE = 6,
00147 };
00148
00149 enum L4_icu_ctl_op
00150 {
00151     L4_ICU_CTL_UNMASK = 0,
00152     L4_ICU_CTL_MASK = 1
00153 };
00154
00155
00163 typedef struct l4_icu_info_t
00164 {
00170     unsigned features;
00171
00175     unsigned nr_irqs;
00176
00180     unsigned nr_msis;
00181 } l4_icu_info_t;
00182
00184 typedef struct l4_icu_msi_info_t
00185 {
00187     l4_uint64_t msi_addr;
00189     l4_uint32_t msi_data;
00190 } l4_icu_msi_info_t;
00191

```

```

00219 L4_INLINE l4_msgtag_t
00220 l4_icu_bind(l4_cap_idx_t icu, unsigned irqnum, l4_cap_idx_t irq) L4_NOTHROW;
00221
00222 L4_INLINE l4_msgtag_t
00223 l4_icu_bind_u(l4_cap_idx_t icu, unsigned irqnum, l4_cap_idx_t irq,
00230 l4_utcb_t *utcb) L4_NOTHROW;
00231
00242 L4_INLINE l4_msgtag_t
00243 l4_icu_unbind(l4_cap_idx_t icu, unsigned irqnum, l4_cap_idx_t irq) L4_NOTHROW;
00244
00251 L4_INLINE l4_msgtag_t
00252 l4_icu_unbind_u(l4_cap_idx_t icu, unsigned irqnum, l4_cap_idx_t irq,
00253 l4_utcb_t *utcb) L4_NOTHROW;
00254
00265 L4_INLINE l4_msgtag_t
00266 l4_icu_set_mode(l4_cap_idx_t icu, unsigned irqnum, l4_umword_t mode) L4_NOTHROW;
00267
00274 L4_INLINE l4_msgtag_t
00275 l4_icu_set_mode_u(l4_cap_idx_t icu, unsigned irqnum, l4_umword_t mode,
00276 l4_utcb_t *utcb) L4_NOTHROW;
00277
00286 L4_INLINE l4_msgtag_t
00287 l4_icu_info(l4_cap_idx_t icu, l4_icu_info_t *info) L4_NOTHROW;
00288
00295 L4_INLINE l4_msgtag_t
00296 l4_icu_info_u(l4_cap_idx_t icu, l4_icu_info_t *info,
00297 l4_utcb_t *utcb) L4_NOTHROW;
00298
00305 L4_INLINE l4_msgtag_t
00306 l4_icu_msi_info(l4_cap_idx_t icu, unsigned irqnum, l4_uint64_t source,
00307 l4_icu_msi_info_t *msi_info) L4_NOTHROW;
00308
00315 L4_INLINE l4_msgtag_t
00316 l4_icu_msi_info_u(l4_cap_idx_t icu, unsigned irqnum, l4_uint64_t source,
00317 l4_icu_msi_info_t *msi_info, l4_utcb_t *utcb) L4_NOTHROW;
00318
00319
00337 L4_INLINE l4_msgtag_t
00338 l4_icu_unmask(l4_cap_idx_t icu, unsigned irqnum, l4_umword_t *label,
00339 l4_timeout_t to) L4_NOTHROW;
00340
00347 L4_INLINE l4_msgtag_t
00348 l4_icu_unmask_u(l4_cap_idx_t icu, unsigned irqnum, l4_umword_t *label,
00349 l4_timeout_t to, l4_utcb_t *utcb) L4_NOTHROW;
00350
00368 L4_INLINE l4_msgtag_t
00369 l4_icu_mask(l4_cap_idx_t icu, unsigned irqnum, l4_umword_t *label,
00370 l4_timeout_t to) L4_NOTHROW;
00371
00378 L4_INLINE l4_msgtag_t
00379 l4_icu_mask_u(l4_cap_idx_t icu, unsigned irqnum, l4_umword_t *label,
00380 l4_timeout_t to, l4_utcb_t *utcb) L4_NOTHROW;
00381
00385 L4_INLINE l4_msgtag_t
00386 l4_icu_control_u(l4_cap_idx_t icu, unsigned irqnum, unsigned op,
00387 l4_umword_t *label, l4_timeout_t to,
00388 l4_utcb_t *utcb) L4_NOTHROW;
00389
00390
00391 /*****
00392 * Implementations
00393 */
00394
00395 L4_INLINE l4_msgtag_t
00396 l4_icu_bind_u(l4_cap_idx_t icu, unsigned irqnum, l4_cap_idx_t irq,
00397 l4_utcb_t *utcb) L4_NOTHROW
00398 {
00399     l4_msg_regs_t *m = l4_utcb_mr_u(utcb);
00400     m->mr[0] = L4_ICU_OP_BIND;
00401     m->mr[1] = irqnum;
00402     m->mr[2] = l4_map_obj_control(0, 0);
00403     m->mr[3] = l4_obj_fpage(irq, 0, L4_CAP_FPAGE_RWS).raw;
00404     return l4_ipc_call(icu, utcb, l4_msgtag(L4_PROTO_IRQ, 2, 1, 0), L4_IPC_NEVER);
00405 }
00406
00407 L4_INLINE l4_msgtag_t
00408 l4_icu_unbind_u(l4_cap_idx_t icu, unsigned irqnum, l4_cap_idx_t irq,
00409 l4_utcb_t *utcb) L4_NOTHROW
00410 {
00411     l4_msg_regs_t *m = l4_utcb_mr_u(utcb);
00412     m->mr[0] = L4_ICU_OP_UNBIND;
00413     m->mr[1] = irqnum;
00414     m->mr[2] = l4_map_obj_control(0, 0);
00415     m->mr[3] = l4_obj_fpage(irq, 0, L4_CAP_FPAGE_RWS).raw;
00416     return l4_ipc_call(icu, utcb, l4_msgtag(L4_PROTO_IRQ, 2, 1, 0), L4_IPC_NEVER);
00417 }
00418

```

```

00419 L4_INLINE l4_msgtag_t
00420 l4_icu_info_u(l4_cap_idx_t icu, l4_icu_info_t *info,
00421              l4_utcb_t *utcb) L4_NOTHROW
00422 {
00423     l4_msgtag_t res;
00424     l4_msg_regs_t *m = l4_utcb_mr_u(utcb);
00425     m->mr[0] = L4_ICU_OP_INFO;
00426     res = l4_ipc_call(icu, utcb, l4_msgtag(L4_PROTO_IRQ, 1, 0, 0), L4_IPC_NEVER);
00427     info->features = m->mr[0];
00428     info->nr_irqs = m->mr[1];
00429     info->nr_msis = m->mr[2];
00430     return res;
00431 }
00432
00433 L4_INLINE l4_msgtag_t
00434 l4_icu_msi_info_u(l4_cap_idx_t icu, unsigned irqnum, l4_uint64_t source,
00435                  l4_icu_msi_info_t *msi_info, l4_utcb_t *utcb) L4_NOTHROW
00436 {
00437     l4_msgtag_t res;
00438     l4_msg_regs_t *m = l4_utcb_mr_u(utcb);
00439     m->mr[0] = L4_ICU_OP_MSI_INFO;
00440     m->mr[1] = irqnum;
00441     m->mr64[l4_utcb_mr64_idx(2)] = source;
00442     res = l4_ipc_call(icu, utcb, l4_msgtag(L4_PROTO_IRQ,
00443                                           2 + 1 * sizeof(l4_uint64_t)
00444                                           / sizeof(l4_umword_t),
00445                                           0, 0), L4_IPC_NEVER);
00446     if (L4_UNLIKELY(l4_msgtag_has_error(res)))
00447         return res;
00448
00449     if (L4_UNLIKELY(l4_msgtag_words(res) * sizeof(l4_umword_t) < sizeof(*msi_info)))
00450         return res;
00451
00452     __builtin_memcpy(msi_info, &m->mr[0], sizeof(*msi_info));
00453     return res;
00454 }
00455
00456 L4_INLINE l4_msgtag_t
00457 l4_icu_set_mode_u(l4_cap_idx_t icu, unsigned irqnum, l4_umword_t mode,
00458                  l4_utcb_t *utcb) L4_NOTHROW
00459 {
00460     l4_msg_regs_t *mr = l4_utcb_mr_u(utcb);
00461     mr->mr[0] = L4_ICU_OP_SET_MODE;
00462     mr->mr[1] = irqnum;
00463     mr->mr[2] = mode;
00464     return l4_ipc_call(icu, utcb, l4_msgtag(L4_PROTO_IRQ, 3, 0, 0), L4_IPC_NEVER);
00465 }
00466
00467 L4_INLINE l4_msgtag_t
00468 l4_icu_control_u(l4_cap_idx_t icu, unsigned irqnum, unsigned op,
00469                  l4_umword_t *label, l4_timeout_t to,
00470                  l4_utcb_t *utcb) L4_NOTHROW
00471 {
00472     l4_msg_regs_t *m = l4_utcb_mr_u(utcb);
00473     m->mr[0] = L4_ICU_OP_UNMASK + op;
00474     m->mr[1] = irqnum;
00475     if (label)
00476         return l4_ipc_send_and_wait(icu, utcb, l4_msgtag(L4_PROTO_IRQ, 2, 0, 0),
00477                                     label, to);
00478     else
00479         return l4_ipc_send(icu, utcb, l4_msgtag(L4_PROTO_IRQ, 2, 0, 0), to);
00480 }
00481
00482 L4_INLINE l4_msgtag_t
00483 l4_icu_mask_u(l4_cap_idx_t icu, unsigned irqnum, l4_umword_t *label,
00484               l4_timeout_t to, l4_utcb_t *utcb) L4_NOTHROW
00485 { return l4_icu_control_u(icu, irqnum, L4_ICU_CTL_MASK, label, to, utcb); }
00486
00487 L4_INLINE l4_msgtag_t
00488 l4_icu_unmask_u(l4_cap_idx_t icu, unsigned irqnum, l4_umword_t *label,
00489                 l4_timeout_t to, l4_utcb_t *utcb) L4_NOTHROW
00490 { return l4_icu_control_u(icu, irqnum, L4_ICU_CTL_UNMASK, label, to, utcb); }
00491
00492
00493
00494
00495 L4_INLINE l4_msgtag_t
00496 l4_icu_bind(l4_cap_idx_t icu, unsigned irqnum, l4_cap_idx_t irq) L4_NOTHROW
00497 { return l4_icu_bind_u(icu, irqnum, irq, l4_utcb()); }
00498
00499 L4_INLINE l4_msgtag_t
00500 l4_icu_unbind(l4_cap_idx_t icu, unsigned irqnum, l4_cap_idx_t irq) L4_NOTHROW
00501 { return l4_icu_unbind_u(icu, irqnum, irq, l4_utcb()); }
00502
00503 L4_INLINE l4_msgtag_t
00504 l4_icu_info(l4_cap_idx_t icu, l4_icu_info_t *info) L4_NOTHROW
00505 { return l4_icu_info_u(icu, info, l4_utcb()); }

```

```

00506
00507 L4_INLINE l4_msgtag_t
00508 l4_icu_msi_info(l4_cap_idx_t icu, unsigned irqnum, l4_uint64_t source,
00509                l4_icu_msi_info_t *msi_info) L4_NOTHROW
00510 { return l4_icu_msi_info_u(icu, irqnum, source, msi_info, l4_utcb()); }
00511
00512 L4_INLINE l4_msgtag_t
00513 l4_icu_unmask(l4_cap_idx_t icu, unsigned irqnum, l4_umword_t *label,
00514              l4_timeout_t to) L4_NOTHROW
00515 { return l4_icu_control_u(icu, irqnum, L4_ICU_CTL_UNMASK, label, to, l4_utcb()); }
00516
00517 L4_INLINE l4_msgtag_t
00518 l4_icu_mask(l4_cap_idx_t icu, unsigned irqnum, l4_umword_t *label,
00519             l4_timeout_t to) L4_NOTHROW
00520 { return l4_icu_control_u(icu, irqnum, L4_ICU_CTL_MASK, label, to, l4_utcb()); }
00521
00522 L4_INLINE l4_msgtag_t
00523 l4_icu_set_mode(l4_cap_idx_t icu, unsigned irqnum, l4_umword_t mode) L4_NOTHROW
00524 {
00525     return l4_icu_set_mode_u(icu, irqnum, mode, l4_utcb());
00526 }

```

## 16.507 iommu

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00002 /* \file
00003  * IO-MMU interface description.
00004  */
00005 #pragma once
00006
00007 #include <l4/sys/cxx/ipc_iface>
00008
00009 namespace L4 {
00021 class Iommu :
00022     public Kobject_x<Iommu, Proto_t<L4_PROTO_IOMMU>, Type_info::Demand_t<1> >
00023 {
00024 public:
00037     L4_INLINE_RPC(
00038         l4_msgtag_t, bind, (l4_uint64_t src_id, Ipc::Cap<Task> dma_space));
00039
00050     L4_INLINE_RPC(
00051         l4_msgtag_t, unbind, (l4_uint64_t src_id, Ipc::Cap<Task> dma_space));
00052
00053     typedef Typeid::Rpc_code<l4_umword_t>::F<bind_t, unbind_t> Rpcs;
00054 };
00055
00056 }

```

## 16.508 ipc.h

```

00001
00006 /*
00007  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00008  *      Alexander Warg <warg@os.inf.tu-dresden.de>,
00009  *      Frank Mehnert <fm3@os.inf.tu-dresden.de>,
00010  *      Torsten Frenzel <frenzel@os.inf.tu-dresden.de>
00011  *      economic rights: Technische Universität Dresden (Germany)
00012  *
00013  * License: see LICENSE.spdx (in this directory or the directories above)
00014  */
00015 #ifndef __L4SYS__INCLUDE__ARCH_AMD64__L4API_L4F__IPC_H__
00016 #define __L4SYS__INCLUDE__ARCH_AMD64__L4API_L4F__IPC_H__
00017
00018 L4_INLINE l4_msgtag_t
00019 l4_ipc(l4_cap_idx_t dest, l4_utcb_t *utcb,
00020        l4_umword_t flags,
00021        l4_umword_t slabel,
00022        l4_msgtag_t tag,
00023        l4_umword_t *rlabel,
00024        l4_timeout_t timeout) L4_NOTHROW
00025 {
00026     l4_umword_t dummy, dummy2;
00027     register l4_umword_t to __asm__("r8") = timeout.raw;
00028
00029     (void)utcb;
00030
00031     __asm__ __volatile__
00032     ("syscall"

```

```

00033     :
00034     "=d" (dummy2),
00035     "=S" (slabel),
00036     "=D" (dummy),
00037     "=a" (tag.raw)
00038     :
00039     "S" (slabel),
00040     "r" (to),
00041     "a" (tag.raw),
00042     "d" (dest | flags)
00043     :
00044     "memory", "cc", "rcx", "r11", "r15"
00045     );
00046
00047     if (rlabel)
00048         *rlabel = slabel;
00049
00050     return tag;
00051 }
00052
00053 #endif /* ! __L4SYS__INCLUDE__ARCH_AMD64__L4API_L4F__IPC_H__ */

```

## 16.509 ipc.h

```

00001
00006 /*
00007  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00008  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00009  *      economic rights: Technische Universität Dresden (Germany)
00010  *
00011  * License: see LICENSE.spdx (in this directory or the directories above)
00012  */
00013 #pragma once
00014
00015 #include <l4/sys/compiler.h>
00016 #include <l4/sys/syscall_defs.h>
00017
00018 L4_INLINE l4_msgtag_t
00019 l4_ipc(l4_cap_idx_t dest, l4_utcb_t *utcb,
00020        l4_umword_t flags,
00021        l4_umword_t slabel,
00022        l4_msgtag_t tag,
00023        l4_umword_t *rlabel,
00024        l4_timeout_t timeout) L4_NOTHROW
00025 {
00026     register l4_umword_t _dest    __asm__("r2") = dest | flags;
00027     register l4_umword_t _timeout __asm__("r3") = timeout.raw;
00028     register l4_mword_t _tag      __asm__("r0") = tag.raw;
00029     register l4_umword_t _label   __asm__("r4") = slabel;
00030     (void)utcb;
00031
00032     __asm__ __volatile__
00033     ("type __l4_sys_syscall, #function\n"
00034      "mov r5, %[sc]          \n"
00035      "blx __l4_sys_syscall  \n"
00036      :
00037      "+r" (_dest),
00038      "+r" (_timeout),
00039      "+r" (_label),
00040      "+r" (_tag)
00041      :
00042      [sc] "i" (L4_SYSCALL_INVOKE)
00043      :
00044      "cc", "memory", "r5", "ip", "lr");
00045
00046     if (rlabel)
00047         *rlabel = _label;
00048     tag.raw = _tag;
00049
00050     return tag;
00051 }

```

## 16.510 ipc.h

```

00001
00006 /*
00007  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00008  *      Alexander Warg <warg@os.inf.tu-dresden.de>

```

```

00009  *      economic rights: Technische Universität Dresden (Germany)
00010  *
00011  * License: see LICENSE.spdx (in this directory or the directories above)
00012  */
00013 #pragma once
00014
00015 #include <l4/sys/compiler.h>
00016
00017 L4_BEGIN_DECLS
00018
00019 struct __l4_sys_syscall_res
00020 {
00021     l4_mword_t tag;
00022     l4_umword_t label;
00023 };
00024
00025 extern struct __l4_sys_syscall_res
00026 __l4_sys_syscall(l4_mword_t tag,
00027                 l4_umword_t slabel,
00028                 l4_umword_t dest,
00029                 l4_umword_t timeout) L4_NOTHROW;
00030
00031 L4_END_DECLS
00032
00033 L4_INLINE l4_msgtag_t
00034 l4_ipc(l4_cap_idx_t dest, l4_utcb_t *utcb,
00035        l4_umword_t flags,
00036        l4_umword_t slabel,
00037        l4_msgtag_t tag,
00038        l4_umword_t *rlabel,
00039        l4_timeout_t timeout) L4_NOTHROW
00040 {
00041     // No need for memory clobbers. The compiler has to assume that all global
00042     // data is read/written because __l4_sys_syscall is implemented in a
00043     // different translation unit.
00044     struct __l4_sys_syscall_res res
00045         = __l4_sys_syscall(tag.raw, slabel, dest | flags, timeout.raw);
00046
00047     (void)utcb;
00048
00049     if (rlabel)
00050         *rlabel = res.label;
00051     tag.raw = res.tag;
00052
00053     return tag;
00054 }

```

## 16.511 l4/sys/ipc.h File Reference

Common IPC interface.


```

#include <l4/sys/types.h>
#include <l4/sys/utcb.h>
#include <l4/sys/err.h>
#include <l4/sys/arch/ipc.h>


```



Include dependency graph for ipc.h:



This graph shows which files directly or indirectly include this file:



## Enumerations

- enum `l4_ipc_tcr_error_t` {
  - `L4_IPC_ERROR_MASK` = 0x1F , `L4_IPC_SND_ERR_MASK` = 0x01 , `L4_IPC_ENOT_EXISTENT` = 0x04 ,
  - `L4_IPC_RETIMEOUT` = 0x03 ,
  - `L4_IPC_SETIMEOUT` = 0x02 , `L4_IPC_RECANCELED` = 0x07 , `L4_IPC_SECANCELED` = 0x06 ,
  - `L4_IPC_REMAPFAILED` = 0x11 ,
  - `L4_IPC_SEMAPFAILED` = 0x10 , `L4_IPC_RESNDPFTO` = 0x0b , `L4_IPC_SESNDPFTO` = 0x0a ,
  - `L4_IPC_RERCVPFTO` = 0x0d ,
  - `L4_IPC_SERCVPFTO` = 0x0c , `L4_IPC_REABORTED` = 0x0f , `L4_IPC_SEABORTED` = 0x0e ,
  - `L4_IPC_REMSGCUT` = 0x09 ,
  - `L4_IPC_SEMSGCUT` = 0x08 }

*Error codes in the error TCR.*

## Functions

- `l4_umword_t l4_ipc_error (l4_msgtag_t tag, l4_utcb_t *utcb) L4_NOTHROW`  
*Get the IPC error code for an IPC operation.*
- `l4_ret_t l4_error (l4_msgtag_t tag) L4_NOTHROW`

- Get IPC error code if any or message tag label otherwise for an IPC call.*

  - `int l4_ipc_is_snd_error (l4_utcb_t *utcb) L4_NOTHROW`  
*Returns whether an error occurred in send phase of an invocation.*
  - `int l4_ipc_is_rcv_error (l4_utcb_t *utcb) L4_NOTHROW`  
*Returns whether an error occurred in receive phase of an invocation.*
  - `int l4_ipc_error_code (l4_utcb_t *utcb) L4_NOTHROW`  
*Get the error condition of the last invocation from the TCR.*
  - `L4_CONSTEXPR l4_ret_t l4_ipc_to_errno (unsigned long ipc_error_code) L4_NOTHROW`  
*Get a negative error code for the given IPC error code.*
  - `l4_msgtag_t l4_ipc_send (l4_cap_idx_t dest, l4_utcb_t *utcb, l4_msgtag_t tag, l4_timeout_t timeout) L4_NOTHROW`  
*Send a message to an object (do **not** wait for a reply).*
  - `l4_msgtag_t l4_ipc_wait (l4_utcb_t *utcb, l4_umword_t *label, l4_timeout_t timeout) L4_NOTHROW`  
*Wait for an incoming message from any possible sender.*
  - `l4_msgtag_t l4_ipc_receive (l4_cap_idx_t object, l4_utcb_t *utcb, l4_timeout_t timeout) L4_NOTHROW`  
*Wait for a message from a specific source.*
  - `l4_msgtag_t l4_ipc_call (l4_cap_idx_t object, l4_utcb_t *utcb, l4_msgtag_t tag, l4_timeout_t timeout) L4_NOTHROW`  
*Object call (usual invocation).*
  - `l4_msgtag_t l4_ipc_reply_and_wait (l4_utcb_t *utcb, l4_msgtag_t tag, l4_umword_t *label, l4_timeout_t timeout) L4_NOTHROW`  
*Reply and wait operation (uses the reply capability).*
  - `l4_msgtag_t l4_ipc_send_and_wait (l4_cap_idx_t dest, l4_utcb_t *utcb, l4_msgtag_t tag, l4_umword_t *label, l4_timeout_t timeout) L4_NOTHROW`  
*Send a message and do an open wait.*
  - `l4_msgtag_t l4_ipc (l4_cap_idx_t dest, l4_utcb_t *utcb, l4_umword_t flags, l4_umword_t slabel, l4_msgtag_t tag, l4_umword_t *rlabel, l4_timeout_t timeout) L4_NOTHROW`  
*Generic L4 object invocation.*
  - `l4_msgtag_t l4_ipc_sleep (l4_timeout_t timeout) L4_NOTHROW`  
*Sleep for an amount of time.*
  - `l4_msgtag_t l4_ipc_sleep_ms (l4_uint32_t ms) L4_NOTHROW`  
*Sleep for a certain amount of milliseconds.*
  - `l4_msgtag_t l4_ipc_sleep_us (l4_uint64_t us) L4_NOTHROW`  
*Sleep for a certain amount of microseconds.*
  - `int l4_sndfpage_add (l4_fpage_t const snd_fpage, unsigned long snd_base, l4_msgtag_t *tag) L4_NOTHROW`  
*Add a flexpage to be sent to the UTCB.*

### 16.511.1 Detailed Description

Common IPC interface.

Definition in file [ipc.h](#).

## 16.511.2 Function Documentation

### 16.511.2.1 l4\_ipc\_to\_errno()

```
L4_CONSTEXPR l4_ret_t l4_ipc_to_errno (
    unsigned long ipc_error_code) [inline]
```

Get a negative error code for the given IPC error code.

#### Parameters

<i>ipc_error_code</i>	IPC error code as delivered by the kernel. (or returned by the <a href="#">l4_ipc_error_code()</a> function).
-----------------------	---

#### Returns

negative error code in the range of [L4\\_EIPC\\_LO](#) to [L4\\_EIPC\\_HI](#).

Definition at line 565 of file [ipc.h](#).

References [L4\\_EIPC\\_LO](#), and [L4\\_NOTHROW](#).

## 16.512 ipc.h

[Go to the documentation of this file.](#)

```
00001
00006 /*
00007  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00008  *      Alexander Warg <warg@os.inf.tu-dresden.de>,
00009  *      Björn Döbel <doebel@os.inf.tu-dresden.de>,
00010  *      Torsten Frenzel <frenzel@os.inf.tu-dresden.de>
00011  *      economic rights: Technische Universität Dresden (Germany)
00012  *
00013  * License: see LICENSE.spdx (in this directory or the directories above)
00014  */
00015 #ifndef __L4SYS__INCLUDE__L4API_FIASCO__IPC_H__
00016 #define __L4SYS__INCLUDE__L4API_FIASCO__IPC_H__
00017
00018 #include <l4/sys/types.h>
00019 #include <l4/sys/utcb.h>
00020 #include <l4/sys/err.h>
00021
00061
00062 /*****
00063  *** IPC result checking
00064  *****/
00065
00073
00081 enum l4_ipc_tcr_error_t
00082 {
00083     L4_IPC_ERROR_MASK           = 0x1F,
00084     L4_IPC_SND_ERR_MASK        = 0x01,
00085
00086     L4_IPC_ENOT_EXISTENT       = 0x04,
00089     L4_IPC_RETIMEOUT           = 0x03,
00092     L4_IPC_SETTIMEOUT          = 0x02,
00095     L4_IPC_RECANCELED          = 0x07,
00098     L4_IPC_SECANCELED          = 0x06,
00101     L4_IPC_REMAPFAILED         = 0x11,
00105     L4_IPC_SEMAPFAILED         = 0x10,
00108     L4_IPC_RESNDPFTO           = 0x0b,
00112     L4_IPC_SESNDPFTO           = 0x0a,
00116     L4_IPC_RERCVPFTO           = 0x0d,
00120     L4_IPC_SERCVPFTO           = 0x0c,
00124     L4_IPC_REABORTED           = 0x0f,
00127     L4_IPC_SEABORTED           = 0x0e,
00136     L4_IPC_REMSGCUT            = 0x09,
00137
```

```

00143 L4_IPC_SEMSGCUT          = 0x08,
00144 };
00145
00146
00157 L4_INLINE l4_umword_t
00158 l4_ipc_error(l4_msgtag_t tag, l4_utcb_t *utcb) L4_NOTHROW;
00159
00160
00177 L4_INLINE l4_ret_t
00178 l4_error(l4_msgtag_t tag) L4_NOTHROW;
00179
00180 L4_INLINE l4_ret_t
00181 l4_error_u(l4_msgtag_t tag, l4_utcb_t *utcb) L4_NOTHROW;
00182
00183 /*****
00184 *** IPC results
00185 *****/
00186
00196 L4_INLINE int l4_ipc_is_snd_error(l4_utcb_t *utcb) L4_NOTHROW;
00197
00207 L4_INLINE int l4_ipc_is_rcv_error(l4_utcb_t *utcb) L4_NOTHROW;
00208
00218 L4_INLINE int l4_ipc_error_code(l4_utcb_t *utcb) L4_NOTHROW;
00219
00226 L4_CONSTEXPR L4_INLINE l4_ret_t
00227 l4_ipc_to_errno(unsigned long ipc_error_code) L4_NOTHROW;
00228
00229
00230 /*****
00231 *** IPC calls
00232 *****/
00233
00262 L4_INLINE l4_msgtag_t
00263 l4_ipc_send(l4_cap_idx_t dest, l4_utcb_t *utcb, l4_msgtag_t tag,
00264             l4_timeout_t timeout) L4_NOTHROW;
00265
00266
00293 L4_INLINE l4_msgtag_t
00294 l4_ipc_wait(l4_utcb_t *utcb, l4_umword_t *label,
00295             l4_timeout_t timeout) L4_NOTHROW;
00296
00297
00324 L4_INLINE l4_msgtag_t
00325 l4_ipc_receive(l4_cap_idx_t object, l4_utcb_t *utcb,
00326               l4_timeout_t timeout) L4_NOTHROW;
00327
00358 L4_INLINE l4_msgtag_t
00359 l4_ipc_call(l4_cap_idx_t object, l4_utcb_t *utcb, l4_msgtag_t tag,
00360             l4_timeout_t timeout) L4_NOTHROW;
00361
00362
00388 L4_INLINE l4_msgtag_t
00389 l4_ipc_reply_and_wait(l4_utcb_t *utcb, l4_msgtag_t tag,
00390                      l4_umword_t *label, l4_timeout_t timeout) L4_NOTHROW;
00391
00420 L4_INLINE l4_msgtag_t
00421 l4_ipc_send_and_wait(l4_cap_idx_t dest, l4_utcb_t *utcb, l4_msgtag_t tag,
00422                     l4_umword_t *label, l4_timeout_t timeout) L4_NOTHROW;
00423
00429
00430 #if 0
00441 L4_INLINE l4_msgtag_t
00442 l4_ipc_wait_next_period(l4_utcb_t *utcb,
00443                        l4_umword_t *label,
00444                        l4_timeout_t timeout);
00445
00446 #endif
00447
00467 L4_ALWAYS_INLINE l4_msgtag_t
00468 l4_ipc(l4_cap_idx_t dest,
00469        l4_utcb_t *utcb,
00470        l4_umword_t flags,
00471        l4_umword_t slabel,
00472        l4_msgtag_t tag,
00473        l4_umword_t *rlabel,
00474        l4_timeout_t timeout) L4_NOTHROW;
00475
00492 L4_INLINE l4_msgtag_t
00493 l4_ipc_sleep(l4_timeout_t timeout) L4_NOTHROW;
00494
00511 L4_INLINE l4_msgtag_t
00512 l4_ipc_sleep_ms(l4_uint32_t ms) L4_NOTHROW;
00513
00530 L4_INLINE l4_msgtag_t
00531 l4_ipc_sleep_us(l4_uint64_t us) L4_NOTHROW;
00532
00547 L4_INLINE int

```

```

00548 l4_sndfpage_add(l4_fpage_t const snd_fpage, unsigned long snd_base,
00549                 l4_msgtag_t *tag) L4_NOTHROW;
00550
00551 /*
00552  * \internal
00553  * \ingroup l4_ipc_api
00554  */
00555 L4_INLINE int
00556 l4_sndfpage_add_u(l4_fpage_t const snd_fpage, unsigned long snd_base,
00557                 l4_msgtag_t *tag, l4_utcb_t *utcb) L4_NOTHROW;
00558
00559
00560 /*****
00561  * Implementations
00562  *****/
00563
00564 L4_CONSTEXPR L4_INLINE l4_ret_t
00565 l4_ipc_to_errno(unsigned long ipc_error_code) L4_NOTHROW
00566 { return -(L4_EIPC_LO + ipc_error_code); }
00567
00568 L4_INLINE l4_msgtag_t
00569 l4_ipc_call(l4_cap_idx_t object, l4_utcb_t *utcb, l4_msgtag_t tag,
00570            l4_timeout_t timeout) L4_NOTHROW
00571 {
00572     return l4_ipc(object, utcb, L4_SYSF_CALL, 0, tag, 0, timeout);
00573 }
00574
00575 L4_INLINE l4_msgtag_t
00576 l4_ipc_reply_and_wait(l4_utcb_t *utcb, l4_msgtag_t tag,
00577                     l4_umword_t *label, l4_timeout_t timeout) L4_NOTHROW
00578 {
00579     return l4_ipc(L4_INVALID_CAP, utcb, L4_SYSF_REPLY_AND_WAIT, 0, tag, label, timeout);
00580 }
00581
00582 L4_INLINE l4_msgtag_t
00583 l4_ipc_send_and_wait(l4_cap_idx_t dest, l4_utcb_t *utcb, l4_msgtag_t tag,
00584                    l4_umword_t *label, l4_timeout_t timeout) L4_NOTHROW
00585 {
00586     return l4_ipc(dest, utcb, L4_SYSF_SEND_AND_WAIT, 0, tag, label, timeout);
00587 }
00588
00589 L4_INLINE l4_msgtag_t
00590 l4_ipc_send(l4_cap_idx_t dest, l4_utcb_t *utcb, l4_msgtag_t tag,
00591            l4_timeout_t timeout) L4_NOTHROW
00592 {
00593     return l4_ipc(dest, utcb, L4_SYSF_SEND, 0, tag, 0, timeout);
00594 }
00595
00596 L4_INLINE l4_msgtag_t
00597 l4_ipc_wait(l4_utcb_t *utcb, l4_umword_t *label,
00598            l4_timeout_t timeout) L4_NOTHROW
00599 {
00600     l4_msgtag_t t;
00601     t.raw = 0;
00602     return l4_ipc(L4_INVALID_CAP, utcb, L4_SYSF_WAIT, 0, t, label, timeout);
00603 }
00604
00605 L4_INLINE l4_msgtag_t
00606 l4_ipc_receive(l4_cap_idx_t object, l4_utcb_t *utcb,
00607              l4_timeout_t timeout) L4_NOTHROW
00608 {
00609     l4_msgtag_t t;
00610     t.raw = 0;
00611     return l4_ipc(object, utcb, L4_SYSF_RECV, 0, t, 0, timeout);
00612 }
00613
00614 L4_INLINE l4_msgtag_t
00615 l4_ipc_sleep(l4_timeout_t timeout) L4_NOTHROW
00616 { return l4_ipc_receive(L4_INVALID_CAP, NULL, timeout); }
00617
00618 L4_INLINE l4_msgtag_t
00619 l4_ipc_sleep_ms(l4_uint32_t ms) L4_NOTHROW
00620 {
00621     l4_uint64_t us = ms * 1000ULL; // cannot overflow because ms < 2^32
00622     return l4_ipc_sleep(l4_timeout(L4_IPC_TIMEOUT_NEVER, l4_timeout_from_us(us)));
00623 }
00624
00625 L4_INLINE l4_msgtag_t
00626 l4_ipc_sleep_us(l4_uint64_t us) L4_NOTHROW
00627 {
00628     return l4_ipc_sleep(l4_timeout(L4_IPC_TIMEOUT_NEVER,
00629                                l4_timeout_from_us(us)));
00629 }
00630
00631
00632 L4_INLINE l4_umword_t
00633 l4_ipc_error(l4_msgtag_t tag, l4_utcb_t *utcb) L4_NOTHROW
00634 {

```

```

00635     if (L4_LIKELY(!l4_msgtag_has_error(tag)))
00636         return 0;
00637     return l4_utcb_tcr_u(utcb)->error & L4_IPC_ERROR_MASK;
00638 }
00639
00640 L4_INLINE l4_ret_t
00641 l4_error_u(l4_msgtag_t tag, l4_utcb_t *u) L4_NOTHROW
00642 {
00643     if (L4_UNLIKELY(l4_msgtag_has_error(tag)))
00644         return l4_ipc_to_errno(l4_utcb_tcr_u(u)->error & L4_IPC_ERROR_MASK);
00645
00646     return l4_msgtag_label(tag);
00647 }
00648
00649 L4_INLINE l4_ret_t
00650 l4_error(l4_msgtag_t tag) L4_NOTHROW
00651 {
00652     return l4_error_u(tag, l4_utcb());
00653 }
00654
00655
00656 L4_INLINE int l4_ipc_is_snd_error(l4_utcb_t *u) L4_NOTHROW
00657 { return (l4_utcb_tcr_u(u)->error & 1) == 0; }
00658
00659 L4_INLINE int l4_ipc_is_rcv_error(l4_utcb_t *u) L4_NOTHROW
00660 { return l4_utcb_tcr_u(u)->error & 1; }
00661
00662 L4_INLINE int l4_ipc_error_code(l4_utcb_t *u) L4_NOTHROW
00663 { return l4_utcb_tcr_u(u)->error & L4_IPC_ERROR_MASK; }
00664
00665
00666 /*
00667  * \internal
00668  * \ingroup l4_ipc_api
00669  */
00670 L4_INLINE int
00671 l4_sndfpage_add_u(l4_fpage_t const snd_fpage, unsigned long snd_base,
00672                  l4_msgtag_t *tag, l4_utcb_t *utcb) L4_NOTHROW
00673 {
00674     l4_msg_regs_t *v = l4_utcb_mr_u(utcb);
00675     int i = l4_msgtag_words(*tag) + 2 * l4_msgtag_items(*tag);
00676
00677     if (i >= L4_UTCB_GENERIC_DATA_SIZE - 1)
00678         return -L4_ENOMEM;
00679
00680     v->mr[i] = snd_base | L4_ITEM_MAP | L4_ITEM_CONT;
00681     v->mr[i + 1] = snd_fpage.raw;
00682
00683     *tag = l4_msgtag(l4_msgtag_label(*tag), l4_msgtag_words(*tag),
00684                     l4_msgtag_items(*tag) + 1, l4_msgtag_flags(*tag));
00685     return 0;
00686 }
00687
00688 L4_INLINE int
00689 l4_sndfpage_add(l4_fpage_t const snd_fpage, unsigned long snd_base,
00690                l4_msgtag_t *tag) L4_NOTHROW
00691 {
00692     return l4_sndfpage_add_u(snd_fpage, snd_base, tag, l4_utcb());
00693 }
00694
00695 #include <l4/sys/arch/ipc.h>
00696
00697 #endif /* ! __L4SYS__INCLUDE__L4API_FIASCO_IPC_H__ */

```

## 16.513 x86/l4/sys/arch/ipc.h File Reference


L4 IPC System Calls, x86.

```

#include <l4/sys/types.h>
#include <l4/sys/consts.h>

```

Include dependency graph for ipc.h:



## Functions

- [l4\\_msgtag\\_t l4\\_ipc](#) ([l4\\_cap\\_idx\\_t](#) dest, [l4\\_utcb\\_t](#) \*u, [l4\\_umword\\_t](#) flags, [l4\\_umword\\_t](#) slabel, [l4\\_msgtag\\_t](#) tag, [l4\\_umword\\_t](#) \*rlabel, [l4\\_timeout\\_t](#) timeout) [L4\\_NOTHROW](#)

*Generic L4 object invocation.*

## 16.513.1 Detailed Description

[L4 IPC System Calls](#), x86.

Definition in file [ipc.h](#).

## 16.514 ipc.h

[Go to the documentation of this file.](#)

```

00001
00006 /*
00007  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00008  *      Alexander Warg <warg@os.inf.tu-dresden.de>,
00009  *      Lars Reuther <reuther@os.inf.tu-dresden.de>
00010  *      economic rights: Technische Universität Dresden (Germany)
00011  *
00012  * License: see LICENSE.spdx (in this directory or the directories above)
00013  */
00014 #ifndef __L4_IPC_H__
00015 #define __L4_IPC_H__
00016
00017 #include <l4/sys/types.h>
00018 #include <l4/sys/consts.h>
00019
00020 #ifdef __PIC__
00021 # define L4S_PIC_SAVE "push %%ebx; "
00022 # define L4S_PIC_RESTORE "pop %%ebx; "
00023 # define L4S_PIC_CLOBBER
00024 # define L4S_PIC_SYSCALL , [func] "m" (__l4sys_invoke_indirect)
00025 extern void (*__l4sys_invoke_indirect)(void);

```

```

00026 # define IPC_SYSENTER      "# indirect sys invoke \n\t" \
00027                               "call *%[func] \n\t"
00028 # define IPC_SYSENTER_ASM    call __l4sys_invoke_direct@plt
00029 #else
00034 #define IPC_SYSENTER      "call __l4sys_invoke_direct \n\t"
00039 #define IPC_SYSENTER_ASM  call __l4sys_invoke_direct
00044 # define L4S_PIC_SAVE
00049 # define L4S_PIC_RESTORE
00054 # define L4S_PIC_CLOBBER , "ebx"
00055 # define L4S_PIC_SYSCALL
00056
00057 #endif
00058
00059 L4_INLINE l4_msgtag_t
00060 l4_ipc(l4_cap_idx_t dest, l4_utcb_t *u,
00061        l4_umword_t flags,
00062        l4_umword_t slabel,
00063        l4_msgtag_t tag,
00064        l4_umword_t *rlabel,
00065        l4_timeout_t timeout) L4_NOTHROW
00066 {
00067     l4_umword_t dummy, dummy1, dummy2;
00068
00069     (void)u;
00070
00071     __asm__ __volatile__
00072     (L4S_PIC_SAVE "push %%ebp; " IPC_SYSENTER " pop %%ebp; " L4S_PIC_RESTORE
00073      :
00074      "=d" (dummy2),
00075      "=S" (slabel),
00076      "=c" (dummy1),
00077      "=D" (dummy),
00078      "=a" (tag.raw)
00079      :
00080      "S" (slabel),
00081      "c" (timeout),
00082      "a" (tag.raw),
00083      "d" (dest | flags)
00084      : L4S_PIC_SYSCALL
00085      :
00086      "memory", "cc" L4S_PIC_CLOBBER
00087      );
00088
00089     if (rlabel)
00090         *rlabel = slabel;
00091
00092     return tag;
00093 }
00094
00095 #endif /* !__L4_IPC_H__ */

```

## 16.515 l4/sys/ipc\_gate File Reference

The C++ IPC gate interface.


```

#include <l4/sys/ipc_gate.h>
#include <l4/sys/capability>
#include <l4/sys/rcv_endpoint>
#include <l4/sys/cxx/ipc_iface>


```



Include dependency graph for ipc\_gate:



This graph shows which files directly or indirectly include this file:



## Data Structures

- class [L4::ipc\\_gate](#)  
The C++ IPC gate interface, see [IPC-Gate API](#) for the C interface.

## Namespaces

- namespace [L4](#)  
[L4](#) low-level kernel interface.

## 16.515.1 Detailed Description

The C++ IPC gate interface.

Definition in file [ipc\\_gate](#).

## 16.516 ipc\_gate

[Go to the documentation of this file.](#)

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00006 /*
00007  * (c) 2009-2010 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00008  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00009  *      economic rights: Technische Universität Dresden (Germany)
00010  *
00011  * License: see LICENSE.spdx (in this directory or the directories above)
00012  */
00013 #pragma once
00014
00015 #include <l4/sys/ipc_gate.h>
00016 #include <l4/sys/capability>
00017 #include <l4/sys/rcv_endpoint>
00018 #include <l4/sys/cxx/ipc_iface>
00019
00020 namespace L4 {
00021
00022 class Thread;
00023
00085 class L4_EXPORT Ipc_gate :
00086     public Kobject_t<Ipc_gate, Rcv_endpoint, L4_PROTO_KOBJECT,
00087         Type_info::Demand_t<1> >
00088 {
00089 public:
00103     L4_INLINE_RPC_OP(L4_IPC_GATE_GET_INFO_OP,
00104         l4_msgtag_t, get_infos, (l4_umword_t *label));
00105
00106     typedef L4::Typeid::Rpcsys<bind_thread_t, get_infos_t> Rpcsys;
00107 };
00108
00109 }

```

## 16.517 l4/sys/ipc\_gate.h File Reference


The C IPC gate interface, see [L4::ipc\\_gate](#) for the C++ interface.

```


#include <l4/sys/utcb.h>
#include <l4/sys/types.h>
#include <l4/sys/rcv_endpoint.h>
#include <l4/sys/ipc.h>

```

Include dependency graph for ipc\_gate.h:



This graph shows which files directly or indirectly include this file:



## Enumerations

- enum [L4\\_ipc\\_gate\\_ops](#) { [L4\\_IPC\\_GATE\\_BIND\\_OP](#) = 0x10 , [L4\\_IPC\\_GATE\\_GET\\_INFO\\_OP](#) = 0x11 }
- Operations on the IPC-gate.*

## Functions

- [l4\\_msgtag\\_t l4\\_ipc\\_gate\\_get\\_infos](#) ([l4\\_cap\\_idx\\_t](#) gate, [l4\\_umword\\_t](#) \*label)
- Get information about the IPC-gate.*

### 16.517.1 Detailed Description

The C IPC gate interface, see [L4::ipc\\_gate](#) for the C++ interface.

IPC gates are used to create secure communication channels between protection domains. An IPC gate can be created using the [Factory](#) interface.

Depending on the permissions of the capability used, an IPC gate forwards IPC to the [Thread](#) the IPC gate is *bound* to (cf. [l4\\_rcv\\_ep\\_bind\\_thread\(\)](#) and [l4\\_rcv\\_ep\\_bind\\_snd\\_destination\(\)](#)). If the capability has the [L4\\_FPAGE\\_C\\_IPCGATE\\_SVR](#) permission, only IPC using a protocol different from the [L4\\_PROTO\\_KOBJECT](#) protocol is forwarded. Without the [L4\\_FPAGE\\_C\\_IPCGATE\\_SVR](#) permission, all IPC is forwarded. The latter is the usual case for a client in a client/server scenario. When not bound to a thread or thread group yet, the forwarded IPC blocks until the IPC gate is bound to a thread or thread group, or the IPC times out.

Forwarded IPC is always forwarded to the userland of the thread the IPC gate is bound to, either directly or indirectly using a thread group. That means, the [Thread](#) interface of that thread is not accessible via an IPC gate. The [IPC-Gate API](#) of an IPC gate is only accessible if the capability used has the [L4\\_FPAGE\\_C\\_IPCGATE\\_SVR](#) permission (cf. previous paragraph). Conversely that means, if the capability used lacks the [L4\\_FPAGE\\_C\\_IPCGATE\\_SVR](#) permission, [IPC-Gate API](#) calls are forwarded to the thread or thread group the IPC gate is bound to instead of being processed by the IPC gate itself. In a client/server scenario, a client should only get IPC gate capabilities without [L4\\_FPAGE\\_C\\_IPCGATE\\_SVR](#) permission so the client cannot tamper with the IPC gate.

When binding an IPC gate to a thread or thread group, a user-defined, kernel protected, machine-word sized payload called the IPC gate's *label* is assigned to the IPC gate (note that the two least significant bits of the label must be zero; cf. [l4\\_rcv\\_ep\\_bind\\_thread\(\)](#) and [l4\\_rcv\\_ep\\_bind\\_snd\\_destination\(\)](#)). When a send-only IPC or call IPC is forwarded via an IPC gate, the label provided by the sender is ignored and replaced by the IPC gate's label where the two least significant bits are set to the [L4\\_CAP\\_FPAGE\\_S](#) and [L4\\_CAP\\_FPAGE\\_W](#) permissions of the capability used. The replaced label is only visible to the thread the IPC gate is bound to upon receive (or to the

selected thread from the thread group the IPC gate is bound to). However, the configured label of an IPC gate can also be queried via [l4\\_ipc\\_gate\\_get\\_infos\(\)](#) if the capability used has the [L4\\_FPAGE\\_C\\_IPCGATE\\_SVR](#) permission.

When deleting an IPC gate or when unbinding it from a thread or thread group, the label of IPC already in flight won't be changed. To ensure that no IPC from this IPC gate is received by a thread with an unexpected label, [l4\\_thread\\_modify\\_sender\\_start\(\)](#) shall be used to change the labels of every pending IPC to that gate. This is also required if the label of an already bound IPC gate is changed. It is not necessary after binding the IPC gate to a thread or thread group for the first time.

When binding a currently bound IPC gate to a new thread or thread group, the same label should be used that was used with the old thread. Otherwise the old and the new thread need to synchronize to avoid IPC messages with unexpected labels.

#### Include File

```
#include <l4/sys/ipc_gate.h>
```

For the C++ interface refer to the [L4::ipc\\_gate](#) documentation.

#### See also

[Object Invocation](#)

Definition in file [ipc\\_gate.h](#).

## 16.518 ipc\_gate.h

[Go to the documentation of this file.](#)

```
00001 /*
00002  * (c) 2009-2010 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00003  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00004  *      economic rights: Technische Universität Dresden (Germany)
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00008
00009 #pragma once
00010
00011 #include <l4/sys/utcb.h>
00012 #include <l4/sys/types.h>
00013 #include <l4/sys/rcv_endpoint.h>
00014
00015 L4_INLINE l4_msgtag_t
00016 l4_ipc_gate_get_infos(l4_cap_idx_t gate, l4_umword_t *label);
00017
00018 L4_INLINE l4_msgtag_t
00019 l4_ipc_gate_get_infos_u(l4_cap_idx_t gate, l4_umword_t *label, l4_utcb_t *utcb);
00020
00021 enum l4_ipc_gate_ops
00022 {
00023     L4_IPC_GATE_BIND_OP      = 0x10,
00024     L4_IPC_GATE_GET_INFO_OP = 0x11,
00025 };
00026
00027 /* IMPLEMENTATION -----*/
00028
00029 #include <l4/sys/ipc.h>
00030
00031 L4_INLINE l4_msgtag_t
00032 l4_ipc_gate_bind_thread_u(l4_cap_idx_t gate,
00033                           l4_cap_idx_t thread, l4_umword_t label,
00034                           l4_utcb_t *utcb)
00035 {
00036     return l4_rcv_ep_bind_thread_u(gate, thread, label, utcb);
00037 }
```

```

00126
00127 L4_INLINE l4_msgtag_t
00128 l4_ipc_gate_bind_snd_destination_u(l4_cap_idx_t gate,
00129                                   l4_cap_idx_t snd_dst, l4_umword_t label,
00130                                   l4_utcb_t *utcb)
00131 {
00132     return l4_rcv_ep_bind_snd_destination_u(gate, snd_dst, label, utcb);
00133 }
00134
00135 L4_INLINE l4_msgtag_t
00136 l4_ipc_gate_get_infos_u(l4_cap_idx_t gate, l4_umword_t *label, l4_utcb_t *utcb)
00137 {
00138     l4_msgtag_t tag;
00139     l4_msg_regs_t *m = l4_utcb_mr_u(utcb);
00140     m->mr[0] = L4_IPC_GATE_GET_INFO_OP;
00141     tag = l4_ipc_call(gate, utcb, l4_msgtag(L4_PROTO_KOBJECT, 1, 0, 0),
00142                     L4_IPC_NEVER);
00143     if (!l4_msgtag_has_error(tag) && l4_msgtag_label(tag) >= 0)
00144         *label = m->mr[0];
00145     return tag;
00146 }
00147
00148
00149
00150
00151 L4_INLINE l4_msgtag_t
00152 l4_ipc_gate_bind_thread(l4_cap_idx_t gate, l4_cap_idx_t thread,
00153                        l4_umword_t label)
00154 {
00155     return l4_rcv_ep_bind_thread_u(gate, thread, label, l4_utcb());
00156 }
00157
00158 L4_INLINE l4_msgtag_t
00159 l4_ipc_gate_bind_snd_destination(l4_cap_idx_t gate, l4_cap_idx_t snd_dst,
00160                                 l4_umword_t label)
00161 {
00162     return l4_rcv_ep_bind_snd_destination_u(gate, snd_dst, label, l4_utcb());
00163 }
00164
00165 L4_INLINE l4_msgtag_t
00166 l4_ipc_gate_get_infos(l4_cap_idx_t gate, l4_umword_t *label)
00167 {
00168     return l4_ipc_gate_get_infos_u(gate, label, l4_utcb());
00169 }

```

## 16.519 l4/sys/irq File Reference


C++ Irq interface.

```


#include <l4/sys/icu.h>
#include <l4/sys/irq.h>
#include <l4/sys/capability>
#include <l4/sys/rcv_endpoint>
#include <l4/sys/cxx/ipc_iface>
#include <l4/sys/cxx/ipc_types>

```

Include dependency graph for irq:



This graph shows which files directly or indirectly include this file:



## Data Structures

- class `L4::Irq_leoi`  
*Interface for sending an unmask message to an object.*
- struct `L4::Triggerable`  
*Interface that allows an object to be triggered by some source.*
- class `L4::Irq`  
*C++ `Irq` interface, see *IRQs* for the C interface.*
- class `L4::Icu`  
*C++ `Icu` interface, see *Interrupt controller* for the C interface.*
- class `L4::Icu::Info`  
*This class encapsulates information about an ICU.*

## Namespaces

- namespace [L4](#)  
*[L4](#) low-level kernel interface.*

### 16.519.1 Detailed Description

C++ Irq interface.

Definition in file [irq](#).

## 16.520 irq

[Go to the documentation of this file.](#)

```
00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00006 /*
00007  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00008  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00009  *      economic rights: Technische Universität Dresden (Germany)
00010  *
00011  * License: see LICENSE.spdx (in this directory or the directories above)
00012  */
00013
00014 #pragma once
00015
00016 #include <l4/sys/icu.h>
00017 #include <l4/sys/irq.h>
00018 #include <l4/sys/capability>
00019 #include <l4/sys/rcv_endpoint>
00020 #include <l4/sys/cxx/ipc_iface>
00021 #include <l4/sys/cxx/ipc_types>
00022
00023 namespace L4 {
00024
00037 class Irq_eoi : public Kobject_0t<Irq_eoi, L4::PROTO_EMPTY>
00038 {
00039 public:
00064     l4_msgtag_t unmask(unsigned irqnum, l4_umword_t *label = 0,
00065                        l4_timeout_t to = L4_IPC_NEVER,
00066                        l4_utcb_t *utcb = l4_utcb()) noexcept
00067     {
00068         return l4_icu_control_u(cap(), irqnum, L4_ICU_CTL_UNMASK, label, to, utcb);
00069     }
00070 };
00071
00079 struct Triggerable : Kobject_t<Triggerable, Irq_eoi, L4_PROTO_IRQ>
00080 {
00091     l4_msgtag_t trigger(l4_utcb_t *utcb = l4_utcb()) noexcept
00092     { return l4_irq_trigger_u(cap(), utcb); }
00093 };
00094
00120 class Irq : public Kobject_2t<Irq, Triggerable, Rcv_endpoint, L4_PROTO_IRQ_SENDER>
00121 {
00122 public:
00123     using Triggerable::unmask;
00124
00158     l4_msgtag_t bind_vcpu(L4::Cap<Thread> const &thread, l4_umword_t cfg,
00159                          l4_utcb_t *utcb = l4_utcb()) noexcept
00160     { return l4_irq_bind_vcpu_u(cap(), thread.cap(), cfg, utcb); }
00161
00176     l4_msgtag_t detach(l4_utcb_t *utcb = l4_utcb()) noexcept
00177     { return l4_irq_detach_u(cap(), utcb); }
00178
00179
00191     l4_msgtag_t receive(l4_timeout_t timeout = L4_IPC_NEVER,
00192                        l4_utcb_t *utcb = l4_utcb()) noexcept
00193     { return l4_irq_receive_u(cap(), timeout, utcb); }
00194
00204     l4_msgtag_t wait(l4_umword_t *label, l4_timeout_t timeout = L4_IPC_NEVER,
00205                     l4_utcb_t *utcb = l4_utcb()) noexcept
00206     { return unmask(-1, label, timeout, utcb); }
00207
00221     l4_msgtag_t unmask(l4_utcb_t *utcb = l4_utcb()) noexcept
```

```

00222 { return unmask(-1, 0, L4_IPC_NEVER, utcb); }
00223 };
00224
00250 class Icu :
00251     public Kobject_t<Icu, Irq_eoi, L4_PROTO_IRQ,
00252         Type_info::Demand_t<1> >
00253 {
00254 public:
00255     enum Mode
00256     {
00257         F_none           = L4_IRQ_F_NONE,
00258         F_level_high     = L4_IRQ_F_LEVEL_HIGH,
00259         F_level_low      = L4_IRQ_F_LEVEL_LOW,
00260         F_pos_edge       = L4_IRQ_F_POS_EDGE,
00261         F_neg_edge       = L4_IRQ_F_NEG_EDGE,
00262         F_both_edge      = L4_IRQ_F_BOTH_EDGE,
00263         F_mask           = L4_IRQ_F_MASK,
00264
00265         F_set_wakeup     = L4_IRQ_F_SET_WAKEUP,
00266         F_clear_wakeup  = L4_IRQ_F_CLEAR_WAKEUP,
00267     };
00268
00269     enum Flags
00270     {
00271         F_msi = L4_ICU_FLAG_MSI
00272     };
00273
00277     class Info : public l4_icu_info_t
00278     {
00279     public:
00281         bool supports_msi() const noexcept { return features & F_msi; }
00282     };
00283
00310     l4_msgtag_t bind(unsigned irqnum, L4::Cap<Triggerable> irq,
00311         l4_utcb_t *utcb = l4_utcb()) noexcept
00312     { return l4_icu_bind_u(cap(), irqnum, irq.cap(), utcb); }
00313
00314     L4_RPC_NF_OP(
00315         L4_ICU_OP_BIND,
00316         l4_msgtag_t, bind, (l4_umword_t irqnum, Ipc::Cap<Irq> irq)
00317     );
00318
00328     l4_msgtag_t unbind(unsigned irqnum, L4::Cap<Triggerable> irq,
00329         l4_utcb_t *utcb = l4_utcb()) noexcept
00330     { return l4_icu_unbind_u(cap(), irqnum, irq.cap(), utcb); }
00331
00332     L4_RPC_NF_OP(
00333         L4_ICU_OP_UNBIND,
00334         l4_msgtag_t, unbind, (l4_umword_t irqnum, Ipc::Cap<Irq> irq)
00335     );
00336
00345     l4_msgtag_t info(l4_icu_info_t *info, l4_utcb_t *utcb = l4_utcb()) noexcept
00346     { return l4_icu_info_u(cap(), info, utcb); }
00347
00348     struct _Info { l4_umword_t features, nr_irqs, nr_msis; };
00349     L4_RPC_NF_OP(L4_ICU_OP_INFO, l4_msgtag_t, info, (_Info *info));
00350
00363     L4_INLINE_RPC_OP(L4_ICU_OP_MSI_INFO,
00364         l4_msgtag_t, msi_info, (l4_umword_t irqnum, l4_uint64_t source,
00365             l4_icu_msi_info_t *msi_info));
00366
00370     l4_msgtag_t control(unsigned irqnum, unsigned op, l4_umword_t *label,
00371         l4_timeout_t to, l4_utcb_t *utcb = l4_utcb()) noexcept
00372     { return l4_icu_control_u(cap(), irqnum, op, label, to, utcb); }
00373
00393     l4_msgtag_t mask(unsigned irqnum,
00394         l4_umword_t *label = 0,
00395         l4_timeout_t to = L4_IPC_NEVER,
00396         l4_utcb_t *utcb = l4_utcb()) noexcept
00397     { return l4_icu_mask_u(cap(), irqnum, label, to, utcb); }
00398
00399     L4_RPC_NF_OP(
00400         L4_ICU_OP_MASK,
00401         l4_msgtag_t, mask, (l4_umword_t irqnum),
00402         L4::Ipc::Send_only
00403     );
00404
00405
00406     L4_RPC_NF_OP(
00407         L4_ICU_OP_UNMASK,
00408         l4_msgtag_t, unmask, (l4_umword_t irqnum),
00409         L4::Ipc::Send_only
00410     );
00411
00421     l4_msgtag_t set_mode(unsigned irqnum, l4_umword_t mode,
00422         l4_utcb_t *utcb = l4_utcb()) noexcept
00423     { return l4_icu_set_mode_u(cap(), irqnum, mode, utcb); }

```



```

00424
00425 L4_RPC_NF_OP (
00426     L4_ICU_OP_SET_MODE,
00427     l4_msgtag_t, set_mode, (l4_umword_t irqnum, l4_umword_t mode)
00428 );
00429
00430 typedef L4::Typeid::Rpcsys<
00431     bind_t, unbind_t, info_t, msi_info_t, unmask_t, mask_t, set_mode_t
00432 > Rpcsys;
00433 };
00434
00435 }

```

## 16.521 l4/sys/kdebug.h File Reference


Functionality for invoking the kernel debugger.

```


#include <l4/sys/compiler.h>
#include <l4/sys/consts.h>
#include <l4/sys/ipc.h>

```

Include dependency graph for kdebug.h:



This graph shows which files directly or indirectly include this file:



## Enumerations

- enum [l4\\_kdebug\\_group\\_t](#)  
*Opcode groups for operations that can be invoked on the base debugger capability.*
- enum [l4\\_kdebug\\_ops\\_t](#)  
*Op-codes for operations that can be invoked on the base debugger capability.*

## Functions

- void [l4\\_kd\\_enter](#) (char const \*text) [L4\\_NOTHROW](#)  
*Enter the kernel debugger.*
- [l4\\_msgtag\\_t](#) [\\_\\_l4\\_kdebug\\_op](#) (unsigned op) [L4\\_NOTHROW](#)  
*Invoke a nullary operation on the base debugger capability.*
- [l4\\_msgtag\\_t](#) [\\_\\_l4\\_kdebug\\_text](#) (unsigned op, char const \*text, unsigned len) [L4\\_NOTHROW](#)  
*Invoke a text output operation on the base debugger capability.*
- [l4\\_msgtag\\_t](#) [\\_\\_l4\\_kdebug\\_3\\_text](#) (unsigned op, char const \*text, unsigned len, [l4\\_umword\\_t](#) v1, [l4\\_umword\\_t](#) v2, [l4\\_umword\\_t](#) v3) [L4\\_NOTHROW](#)  
*Invoke a text output operation with 3 additional machine word arguments on the base debugger capability.*
- [l4\\_msgtag\\_t](#) [\\_\\_l4\\_kdebug\\_op\\_1](#) (unsigned op, [l4\\_mword\\_t](#) val) [L4\\_NOTHROW](#)  
*Invoke an unary operation on the base debugger capability.*
- void [l4\\_kd\\_outnstring](#) (char const \*text, unsigned len)  
*Output a fixed-length string via the kernel debugger.*
- void [l4\\_kd\\_outstring](#) (char const \*text)  
*Output a string via the kernel debugger.*
- void [l4\\_kd\\_outchar](#) (char c)  
*Output a single character via the kernel debugger.*
- void [l4\\_kd\\_outumword](#) ([l4\\_umword\\_t](#) number)  
*Output a hexadecimal unsigned machine word via the kernel debugger.*
- void [l4\\_kd\\_outhex64](#) ([l4\\_uint64\\_t](#) number)  
*Output a 64-bit unsigned hexadecimal number via the kernel debugger.*
- void [l4\\_kd\\_outhex32](#) ([l4\\_uint32\\_t](#) number)  
*Output a 32-bit unsigned hexadecimal number via the kernel debugger.*
- void [l4\\_kd\\_outhex20](#) ([l4\\_uint32\\_t](#) number)  
*Output a 20-bit unsigned hexadecimal number via the kernel debugger.*
- void [l4\\_kd\\_outhex16](#) ([l4\\_uint16\\_t](#) number)  
*Output a 16-bit unsigned hexadecimal number via the kernel debugger.*
- void [l4\\_kd\\_outhex12](#) ([l4\\_uint16\\_t](#) number)  
*Output a 12-bit unsigned hexadecimal number via the kernel debugger.*
- void [l4\\_kd\\_outhex8](#) ([l4\\_uint8\\_t](#) number)  
*Output an 8-bit unsigned hexadecimal number via the kernel debugger.*
- void [l4\\_kd\\_outdec](#) ([l4\\_mword\\_t](#) number)  
*Output a decimal unsigned machine word via the kernel debugger.*

### 16.521.1 Detailed Description

Functionality for invoking the kernel debugger.

Definition in file [kdebug.h](#).

## 16.521.2 Enumeration Type Documentation

### 16.521.2.1 l4\_kdebug\_ops\_t

```
enum l4_kdebug_ops_t
```

Op-codes for operations that can be invoked on the base debugger capability.

See also [\\_\\_ktrace-impl.h](#) for additional op-codes.

Definition at line 44 of file [kdebug.h](#).

## 16.521.3 Function Documentation

### 16.521.3.1 \_\_l4\_kdebug\_3\_text()

```
l4_msgtag_t __l4_kdebug_3_text (
    unsigned op,
    char const * text,
    unsigned len,
    l4_umword_t v1,
    l4_umword_t v2,
    l4_umword_t v3) [inline]
```

Invoke a text output operation with 3 additional machine word arguments on the base debugger capability.

#### Parameters

<i>op</i>	Text output operation code from <a href="#">l4_kdebug_ops_t</a> or a value above 0x200 used by the kernel trace buffer implementation ( <a href="#">__ktrace-impl.h</a> ).
<i>text</i>	Output string.
<i>len</i>	Length of the output string. The maximum length is limited to <a href="#">L4_UTCB_GENERIC_DATA_SIZE</a> - 5 machine words. Output strings longer than this limit will be cropped.
<i>v1</i>	First machine word argument.
<i>v2</i>	Second machine word argument.
<i>v3</i>	Third machine word argument.

#### Return values


<i>Message</i>	tag returned from the IPC on the base debugger capability.
----------------	--

Definition at line 139 of file [kdebug.h](#).

References [L4\\_BASE\\_DEBUGGER\\_CAP](#), [l4\\_bytes\\_to\\_mwords\(\)](#), [l4\\_ipc\\_call\(\)](#), [L4\\_IPC\\_NEVER](#), [l4\\_msgtag\(\)](#), [L4\\_NOTHROW](#), [L4\\_PROTO\\_DEBUGGER](#), [l4\\_utcb\(\)](#), and [l4\\_msg\\_regs\\_t::mr](#).

Referenced by [fiasco\\_tbuf\\_log\\_3val\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 16.521.3.2 \_\_l4\_kdebug\_op()

```
l4_msgtag_t __l4_kdebug_op (
    unsigned op) [inline]
```

Invoke a nullary operation on the base debugger capability.

#### Parameters

<i>op</i>	Nullary operation code from <a href="#">l4_kdebug_ops_t</a> or a value above 0x200 used by the kernel trace buffer implementation ( <a href="#">__ktrace-impl.h</a> ).
-----------	--

#### Return values


<i>Message</i>	tag returned from the IPC on the base debugger capability.
----------------	--

Definition at line 68 of file [kdebug.h](#).


References [L4\\_BASE\\_DEBUGGER\\_CAP](#), [l4\\_ipc\\_call\(\)](#), [L4\\_IPC\\_NEVER](#), [l4\\_msgtag\(\)](#), [L4\\_NOTHROW](#), [L4\\_PROTO\\_DEBUGGER](#), [l4\\_utcb\(\)](#), and [l4\\_msg\\_regs\\_t::mr](#).

Referenced by [fiasco\\_dump\\_kmem\\_stats\(\)](#), [fiasco\\_tbuf\\_clear\(\)](#), and [fiasco\\_tbuf\\_dump\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 16.521.3.3 \_\_l4\_kdebug\_op\_1()

```

l4_msgtag_t __l4_kdebug_op_1 (
    unsigned op,
    l4_mword_t val) [inline]
  
```

Invoke an unary operation on the base debugger capability.

#### Parameters

<i>op</i>	Unary operation code from <a href="#">l4_kdebug_ops_t</a> or a value above 0x200 used by the kernel trace buffer implementation ( <a href="#">__ktrace-impl.h</a> ).
<i>val</i>	Machine word argument to the unary operation.

### Return values


<i>Message</i>	tag returned from the IPC on the base debugger capability.
----------------	--

Definition at line 176 of file [kdebug.h](#).


References [L4\\_BASE\\_DEBUGGER\\_CAP](#), [l4\\_ipc\\_call\(\)](#), [L4\\_IPC\\_NEVER](#), [l4\\_msgtag\(\)](#), [L4\\_NOTHROW](#), [L4\\_PROTO\\_DEBUGGER](#), [l4\\_utcb\(\)](#), and [l4\\_msg\\_regs\\_t::mr](#).

Referenced by [l4\\_kd\\_outchar\(\)](#), [l4\\_kd\\_outdec\(\)](#), [l4\\_kd\\_outhex12\(\)](#), [l4\\_kd\\_outhex16\(\)](#), [l4\\_kd\\_outhex20\(\)](#), [l4\\_kd\\_outhex32\(\)](#), [l4\\_kd\\_outhex64\(\)](#), [l4\\_kd\\_outhex8\(\)](#), and [l4\\_kd\\_outumword\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



#### 16.521.3.4 `__l4_kdebug_text()`

```

l4_msgtag_t __l4_kdebug_text (
    unsigned op,
    char const * text,
    unsigned len) [inline]
  
```

Invoke a text output operation on the base debugger capability.

##### Parameters

<i>op</i>	Text output operation code from <code>l4_kdebug_ops_t</code> or a value above 0x200 used by the kernel trace buffer implementation ( <code>__ktrace-impl.h</code> ).
<i>text</i>	Output string.

<i>len</i>	Length of the output string. The maximum length is limited to <a href="#">L4_UTCB_GENERIC_DATA_SIZE</a> - 2 machine words. Output strings longer than this limit will be cropped.
------------	---

### Return values


<i>Message</i>	tag returned from the IPC on the base debugger capability.
----------------	--

Definition at line 98 of file [kdebug.h](#).


References [L4\\_BASE\\_DEBUGGER\\_CAP](#), [l4\\_bytes\\_to\\_mwords\(\)](#), [l4\\_ipc\\_call\(\)](#), [L4\\_IPC\\_NEVER](#), [l4\\_msgtag\(\)](#), [L4\\_NOTHROW](#), [L4\\_PROTO\\_DEBUGGER](#), [l4\\_utcb\(\)](#), and [l4\\_msg\\_regs\\_t::mr](#).

Referenced by [fiasco\\_tbuf\\_log\(\)](#), [fiasco\\_tbuf\\_log\\_binary\(\)](#), [l4\\_kd\\_enter\(\)](#), and [l4\\_kd\\_outstring\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:





### 16.521.3.5 l4\_kd\_enter()

```
void l4_kd_enter (
    char const * text) [inline]
```

Enter the kernel debugger.

#### Parameters

<i>text</i>	Optional message displayed by the kernel debugger when entered.
-------------	---

Enter the kernel debugger, if configured. An optional message can be passed to the kernel debugger which is printed upon the entering of the debugger.


#### Examples

[examples/sys/singlestep/main.c](#).

Definition at line 204 of file [kdebug.h](#).

References [\\_\\_l4\\_kdebug\\_text\(\)](#), [L4\\_BASE\\_DEBUGGER\\_CAP](#), [L4\\_INLINE](#), [l4\\_ipc\\_call\(\)](#), [L4\\_IPC\\_NEVER](#), [l4\\_msgtag\(\)](#), [L4\\_NOTHROW](#), and [L4\\_PROTO\\_DEBUGGER](#).

Here is the call graph for this function:



### 16.521.3.6 l4\_kd\_outchar()

```
void l4_kd_outchar (
    char c) [inline]
```

Output a single character via the kernel debugger.


#### Parameters

<i>c</i>	Output character.
----------	-------------------

Definition at line 245 of file [kdebug.h](#).

References [\\_\\_l4\\_kdebug\\_op\\_1\(\)](#), and [L4\\_INLINE](#).

Here is the call graph for this function:



### 16.521.3.7 l4\_kd\_outdec()

```
void l4_kd_outdec (
    l4_mword_t number) [inline]
```

Output a decimal unsigned machine word via the kernel debugger.


#### Parameters

<i>number</i>	Output machine word.
---------------	----------------------

Definition at line 334 of file [kdebug.h](#).

References [\\_\\_l4\\_kdebug\\_op\\_1\(\)](#), and [L4\\_INLINE](#).

Here is the call graph for this function:



**16.521.3.8 l4\_kd\_outhex12()**

```
void l4_kd_outhex12 (
    l4_uint16_t number) [inline]
```

Output a 12-bit unsigned hexadecimal number via the kernel debugger.


**Parameters**

<i>number</i>	Output 12-bit number. Only the 12 LSB bits are used.
---------------	--

Definition at line 314 of file [kdebug.h](#).

References [\\_\\_l4\\_kdebug\\_op\\_1\(\)](#), and [L4\\_INLINE](#).

Here is the call graph for this function:

**16.521.3.9 l4\_kd\_outhex16()**

```
void l4_kd_outhex16 (
    l4_uint16_t number) [inline]
```

Output a 16-bit unsigned hexadecimal number via the kernel debugger.


**Parameters**

<i>number</i>	Output 16-bit number.
---------------	-----------------------

Definition at line 304 of file [kdebug.h](#).

References [\\_\\_l4\\_kdebug\\_op\\_1\(\)](#), and [L4\\_INLINE](#).

Here is the call graph for this function:



### 16.521.3.10 l4\_kd\_outhex20()

```
void l4_kd_outhex20 (  
    l4_uint32_t number) [inline]
```

Output a 20-bit unsigned hexadecimal number via the kernel debugger.


#### Parameters

<i>number</i>	Output 20-bit number. Only the 20 LSB bits are used.
---------------	--

Definition at line 294 of file [kdebug.h](#).

References [\\_\\_l4\\_kdebug\\_op\\_1\(\)](#), and [L4\\_INLINE](#).

Here is the call graph for this function:



### 16.521.3.11 l4\_kd\_outhex32()

```
void l4_kd_outhex32 (  
    l4_uint32_t number) [inline]
```

Output a 32-bit unsigned hexadecimal number via the kernel debugger.


#### Parameters

<i>number</i>	Output 32-bit number.
---------------	-----------------------

Definition at line 284 of file [kdebug.h](#).

References [\\_\\_l4\\_kdebug\\_op\\_1\(\)](#), and [L4\\_INLINE](#).

Here is the call graph for this function:



### 16.521.3.12 l4\_kd\_outhex64()

```
void l4_kd_outhex64 (  
    l4_uint64_t number) [inline]
```

Output a 64-bit unsigned hexadecimal number via the kernel debugger.

#### Parameters


<i>number</i>	Output 64-bit number.
---------------	-----------------------

The two 32-bit halves are printed non-atomically.

Definition at line 273 of file [kdebug.h](#).

References [\\_\\_l4\\_kdebug\\_op\\_1\(\)](#), and [L4\\_INLINE](#).

Here is the call graph for this function:



### 16.521.3.13 l4\_kd\_outhex8()

```
void l4_kd_outhex8 (  
    l4_uint8_t number) [inline]
```

Output an 8-bit unsigned hexadecimal number via the kernel debugger.


#### Parameters

<i>number</i>	Output 8-bit number.
---------------	----------------------

Definition at line 324 of file [kdebug.h](#).

References [\\_\\_l4\\_kdebug\\_op\\_1\(\)](#), and [L4\\_INLINE](#).

Here is the call graph for this function:



#### 16.521.3.14 l4\_kd\_outnstring()

```

void l4_kd_outnstring (
    char const * text,
    unsigned len) [inline]
  
```

Output a fixed-length string via the kernel debugger.

#### Parameters


<i>text</i>	Beginning of the output string.
<i>len</i>	Length of the output string. The maximum length is limited to <a href="#">L4_UTCB_GENERIC_DATA_SIZE</a> - 2 machine words. Output strings longer than this limit will be cropped.

Definition at line 226 of file [kdebug.h](#).


References [\\_\\_l4\\_kdebug\\_text\(\)](#), and [L4\\_INLINE](#).

Referenced by [l4\\_kd\\_outstring\(\)](#).

Here is the call graph for this function:



Here is the caller graph for this function:



### 16.521.3.15 l4\_kd\_outstring()

```
void l4_kd_outstring (
    char const * text) [inline]
```

Output a string via the kernel debugger.


#### Parameters

<i>text</i>	Beginning of the output string. The maximum length of the output string is limited to <a href="#">L4_UTCB_GENERIC_DATA_SIZE</a> - 2 machine words. Output strings longer than this limit will be cropped.
-------------	---

Definition at line 237 of file [kdebug.h](#).

References [L4\\_INLINE](#), and [l4\\_kd\\_outnstring\(\)](#).

Here is the call graph for this function:



### 16.521.3.16 l4\_kd\_outumword()

```
void l4_kd_outumword (
    l4_umword_t number) [inline]
```

Output a hexadecimal unsigned machine word via the kernel debugger.

## Parameters


<i>number</i>	Output machine word.
---------------	----------------------

If the machine word is 64 bits long, it is printed non-atomically as two 32-bit numbers.

Definition at line 258 of file [kdebug.h](#).

References [\\_\\_l4\\_kdebug\\_op\\_1\(\)](#), and [L4\\_INLINE](#).

Here is the call graph for this function:



## 16.522 kdebug.h

[Go to the documentation of this file.](#)

```

00001 /*
00002  * (c) 2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>
00003  *     economic rights: Technische Universität Dresden (Germany)
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007
00008 #pragma once
00009
00010
00011 #ifndef __KDEBUG_H__
00012 #define __KDEBUG_H__
00013
00014 #include <l4/sys/compiler.h>
00015 #include <l4/sys/consts.h>
00016 #include <l4/sys/ipc.h>
00017
00018
00019 L4_INLINE void
00020 l4_kd_enter(char const *text) L4_NOTHROW;
00021
00022 enum l4_kdebug_group_t
00023 {
00024     L4_KDEBUG_GROUP_JDB      = 0x000,
00025     L4_KDEBUG_GROUP_KOBJ     = 0x100, // see __kernel_object_impl.h
00026     L4_KDEBUG_GROUP_TRACE    = 0x200, // see __ktrace-impl.h
00027     L4_KDEBUG_GROUP_COV      = 0x400,
00028     L4_KDEBUG_GROUP_DUMP     = 0x500, // see kdump.h
00029 };
00030
00031 enum l4_kdebug_ops_t
00032 {
00033     L4_KDEBUG_ENTER          = L4_KDEBUG_GROUP_JDB + 0,
00034     L4_KDEBUG_OUTCHAR         = L4_KDEBUG_GROUP_JDB + 1,
00035     L4_KDEBUG_OUTNSTRING      = L4_KDEBUG_GROUP_JDB + 2,
00036     L4_KDEBUG_OUTHEX32        = L4_KDEBUG_GROUP_JDB + 3,
00037     L4_KDEBUG_OUTHEX20        = L4_KDEBUG_GROUP_JDB + 4,
00038     L4_KDEBUG_OUTHEX16        = L4_KDEBUG_GROUP_JDB + 5,
00039     L4_KDEBUG_OUTHEX12        = L4_KDEBUG_GROUP_JDB + 6,
00040     L4_KDEBUG_OUTHEX8         = L4_KDEBUG_GROUP_JDB + 7,
00041 };

```



```

00054 L4_KDEBUG_OUTDEC      = L4_KDEBUG_GROUP_JDB + 8,
00055 };
00056
00057
00067 L4_INLINE l4_msgtag_t
00068 __l4_kdebug_op(unsigned op) L4_NOTHROW
00069 {
00070     l4_msgtag_t res;
00071     l4_utcb_t *u = l4_utcb();
00072     l4_msg_regs_t *mr = l4_utcb_mr_u(u);
00073     l4_umword_t mr0 = mr->mr[0];
00074
00075     mr->mr[0] = op;
00076     res = l4_ipc_call(L4_BASE_DEBUGGER_CAP, u,
00077                     l4_msgtag(L4_PROTO_DEBUGGER, 1, 0, 0),
00078                     L4_IPC_NEVER);
00079     mr->mr[0] = mr0;
00080     return res;
00081 }
00082
00097 L4_INLINE l4_msgtag_t
00098 __l4_kdebug_text(unsigned op, char const *text, unsigned len) L4_NOTHROW
00099 {
00100     l4_msg_regs_t store;
00101     l4_msgtag_t res;
00102     l4_utcb_t *u = l4_utcb();
00103     l4_msg_regs_t *mr = l4_utcb_mr_u(u);
00104
00105     if (len > (sizeof(store) - (2 * sizeof(l4_umword_t))))
00106         len = sizeof(store) - (2 * sizeof(l4_umword_t));
00107
00108     __builtin_memcpy(&store, mr, sizeof(store));
00109     mr->mr[0] = op;
00110     mr->mr[1] = len;
00111     __builtin_memcpy(&mr->mr[2], text, len);
00112     res = l4_ipc_call(L4_BASE_DEBUGGER_CAP, u,
00113                     l4_msgtag(L4_PROTO_DEBUGGER,
00114                             l4_bytes_to_mwords(len) + 2, 0, 0),
00115                     L4_IPC_NEVER);
00116     __builtin_memcpy(mr, &store, sizeof(*mr));
00117     return res;
00118 }
00119
00138 L4_INLINE l4_msgtag_t
00139 __l4_kdebug_3_text(unsigned op, char const *text, unsigned len,
00140                   l4_umword_t v1, l4_umword_t v2, l4_umword_t v3) L4_NOTHROW
00141 {
00142     l4_msg_regs_t store;
00143     l4_msgtag_t res;
00144     l4_utcb_t *u = l4_utcb();
00145     l4_msg_regs_t *mr = l4_utcb_mr_u(u);
00146
00147     if (len > (sizeof(store) - (5 * sizeof(l4_umword_t))))
00148         len = sizeof(store) - (5 * sizeof(l4_umword_t));
00149
00150     __builtin_memcpy(&store, mr, sizeof(store));
00151     mr->mr[0] = op;
00152     mr->mr[1] = v1;
00153     mr->mr[2] = v2;
00154     mr->mr[3] = v3;
00155     mr->mr[4] = len;
00156     __builtin_memcpy(&mr->mr[5], text, len);
00157     res = l4_ipc_call(L4_BASE_DEBUGGER_CAP, u,
00158                     l4_msgtag(L4_PROTO_DEBUGGER,
00159                             l4_bytes_to_mwords(len) + 5, 0, 0),
00160                     L4_IPC_NEVER);
00161     __builtin_memcpy(mr, &store, sizeof(*mr));
00162     return res;
00163 }
00164
00175 L4_INLINE l4_msgtag_t
00176 __l4_kdebug_op_1(unsigned op, l4_mword_t val) L4_NOTHROW
00177 {
00178     l4_umword_t m[2];
00179     l4_msgtag_t res;
00180     l4_utcb_t *u = l4_utcb();
00181     l4_msg_regs_t *mr = l4_utcb_mr_u(u);
00182
00183     m[0] = mr->mr[0];
00184     m[1] = mr->mr[1];
00185     mr->mr[0] = op;
00186     mr->mr[1] = val;
00187     res = l4_ipc_call(L4_BASE_DEBUGGER_CAP, u,
00188                     l4_msgtag(L4_PROTO_DEBUGGER, 2, 0, 0),
00189                     L4_IPC_NEVER);
00190     mr->mr[0] = m[0];
00191     mr->mr[1] = m[1];

```

```

00192     return res;
00193 }
00194
00204 L4_INLINE void l4_kd_enter(char const *text) L4_NOTHROW
00205 {
00206     /* special case, enter without any text and use of the UTCB */
00207     if (!text)
00208     {
00209         l4_ipc_call(L4_BASE_DEBUGGER_CAP, 0,
00210                   l4_msgtag(L4_PROTO_DEBUGGER, 0, 0, 0),
00211                   L4_IPC_NEVER);
00212         return;
00213     }
00214
00215     __l4_kdebug_text(L4_KDEBUG_ENTER, text, __builtin_strlen(text));
00216 }
00217
00226 L4_INLINE void l4_kd_outnstring(char const *text, unsigned len)
00227 { __l4_kdebug_text(L4_KDEBUG_OUTNSTRING, text, len); }
00228
00237 L4_INLINE void l4_kd_outstring(char const *text)
00238 { l4_kd_outnstring(text, __builtin_strlen(text)); }
00239
00245 L4_INLINE void l4_kd_outchar(char c)
00246 {
00247     __l4_kdebug_op_1(L4_KDEBUG_OUTCHAR, c);
00248 }
00249
00258 L4_INLINE void l4_kd_outumword(l4_umword_t number)
00259 {
00260     if (sizeof(l4_umword_t) == sizeof(l4_uint64_t))
00261         __l4_kdebug_op_1(L4_KDEBUG_OUTHEX32, (l4_uint64_t)number >> 32);
00262
00263     __l4_kdebug_op_1(L4_KDEBUG_OUTHEX32, number);
00264 }
00265
00273 L4_INLINE void l4_kd_outhex64(l4_uint64_t number)
00274 {
00275     __l4_kdebug_op_1(L4_KDEBUG_OUTHEX32, number >> 32);
00276     __l4_kdebug_op_1(L4_KDEBUG_OUTHEX32, number);
00277 }
00278
00284 L4_INLINE void l4_kd_outhex32(l4_uint32_t number)
00285 {
00286     __l4_kdebug_op_1(L4_KDEBUG_OUTHEX32, number);
00287 }
00288
00294 L4_INLINE void l4_kd_outhex20(l4_uint32_t number)
00295 {
00296     __l4_kdebug_op_1(L4_KDEBUG_OUTHEX20, number);
00297 }
00298
00304 L4_INLINE void l4_kd_outhex16(l4_uint16_t number)
00305 {
00306     __l4_kdebug_op_1(L4_KDEBUG_OUTHEX16, number);
00307 }
00308
00314 L4_INLINE void l4_kd_outhex12(l4_uint16_t number)
00315 {
00316     __l4_kdebug_op_1(L4_KDEBUG_OUTHEX12, number);
00317 }
00318
00324 L4_INLINE void l4_kd_outhex8(l4_uint8_t number)
00325 {
00326     __l4_kdebug_op_1(L4_KDEBUG_OUTHEX8, number);
00327 }
00328
00334 L4_INLINE void l4_kd_outdec(l4_mword_t number)
00335 {
00336     __l4_kdebug_op_1(L4_KDEBUG_OUTDEC, number);
00337 }
00338
00339 #endif //__KDEBUG_H__


```

## 16.523 l4/sys/kdump.h File Reference

Functionality for dumping kernel information.

```
#include <l4/sys/kdebug.h>
```

Include dependency graph for kdump.h:



## Functions

- long [fiasco\\_dump\\_kmem\\_stats](#) (void)  
*Dump kernel memory statistics on console.*

## 16.523.1 Detailed Description

Functionality for dumping kernel information.

Definition in file [kdump.h](#).

## 16.523.2 Function Documentation

### 16.523.2.1 fiasco\_dump\_kmem\_stats()

```
long fiasco_dump_kmem_stats (
    void ) [inline]
```

Dump kernel memory statistics on console.


## Return values

0	Success.
-L4_ENOSYS	Not implemented by kernel.

Definition at line 38 of file [kdump.h](#).

References [\\_\\_l4\\_kdebug\\_op\(\)](#), and [l4\\_error\(\)](#).

Here is the call graph for this function:



## 16.524 kdump.h

[Go to the documentation of this file.](#)

```

00001 /*
00002  * Copyright (C) 2024-2025 Kernkonzept GmbH.
00003  * Author(s): Jan Klötzke <jan.kloetzke@kernkonzept.com>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007
00008 #pragma once
00009
00014
00025
00026 #include <l4/sys/kdebug.h>
00027
00034 L4_INLINE long
00035 fiasco_dump_kmem_stats(void);
00036
00037 L4_INLINE long
00038 fiasco_dump_kmem_stats(void)
00039 {
00040     enum { DUMP_KMEM_STATS = L4_KDEBUG_GROUP_DUMP + 0x00 };
00041     return l4_error(__l4_kdebug_op(DUMP_KMEM_STATS));
00042 }

```

## 16.525 l4/sys/kernel\_object.h File Reference

Kernel object system calls.


```

#include <l4/sys/types.h>
#include <l4/sys/compiler.h>
#include <l4/sys/utcb.h>
#include <l4/sys/__kernel_object_impl.h>


```

```
#include <l4/sys/ipc.h>
```

Include dependency graph for kernel\_object.h:



This graph shows which files directly or indirectly include this file:



## 16.525.1 Detailed Description

Kernel object system calls.

Definition in file [kernel\\_object.h](#).

## 16.526 kernel\_object.h

[Go to the documentation of this file.](#)

```

00001
00005 /*
00006  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00007  *      Alexander Warg <warg@os.inf.tu-dresden.de>,
00008  *      Björn Döbel <doebel@os.inf.tu-dresden.de>
00009  *      economic rights: Technische Universität Dresden (Germany)
00010  *
00011  * License: see LICENSE.spdx (in this directory or the directories above)

```

```

00012  */
00013  #ifndef __L4SYS__KERNEL_OBJECT_H__
00014  #define __L4SYS__KERNEL_OBJECT_H__
00015
00016  #include <l4/sys/types.h>
00017  #include <l4/sys/compiler.h>
00018  #include <l4/sys/utcb.h>
00019
00027
00038  L4_INLINE l4_msgtag_t
00039  l4_invoke_debugger(l4_cap_idx_t obj, l4_msgtag_t tag, l4_utcb_t *utcb) L4_NOTHROW;
00040
00041
00042  /*****
00043   * Implementation
00044   *****/
00045
00046  #include <l4/sys/__kernel_object_impl.h>
00047  #include <l4/sys/ipc.h>
00048
00049  enum L4_kobject_op {
00050      L4_KOBJECT_OP_DEC_REFCNT = 0,
00051      L4_KOBJECT_OP_REGISTER_IRQ,
00052  };
00053
00054  L4_INLINE l4_msgtag_t
00055  l4_kobject_dec_refcnt_u(l4_cap_idx_t obj, l4_mword_t diff, l4_utcb_t *u) L4_NOTHROW;
00056
00057  L4_INLINE l4_msgtag_t
00058  l4_kobject_dec_refcnt(l4_cap_idx_t obj, l4_mword_t diff) L4_NOTHROW;
00059
00060  L4_INLINE l4_msgtag_t
00061  l4_kobject_dec_refcnt_u(l4_cap_idx_t obj, l4_mword_t diff, l4_utcb_t *u) L4_NOTHROW
00062  {
00063      l4_msg_regs_t *m = l4_utcb_mr_u(u);
00064      m->mr[0] = L4_KOBJECT_OP_DEC_REFCNT;
00065      m->mr[1] = diff;
00066      return l4_ipc_call(obj, u, l4_msgtag(L4_PROTO_KOBJECT, 2, 0, 0), L4_IPC_NEVER);
00067  }
00068
00069  L4_INLINE l4_msgtag_t
00070  l4_kobject_dec_refcnt(l4_cap_idx_t obj, l4_mword_t diff) L4_NOTHROW
00071  {
00072      return l4_kobject_dec_refcnt_u(obj, diff, l4_utcb());
00073  }
00074
00075  #endif /* ! __L4SYS__KERNEL_OBJECT_H__ */


```

## 16.527 I4/sys/kip File Reference

```
#include <l4/cxx/static_vector>
```

```
#include <l4/sys/kip.h>
```

Include dependency graph for kip:



## Data Structures

- class [L4::Kip::Mem\\_desc](#)

*Memory descriptors stored in the kernel interface page.*

## Namespaces

- namespace [L4](#)

*[L4](#) low-level kernel interface.*

## 16.527.1 Detailed Description

L4::Kip class, memory descriptors.

### Author

Alexander Warg [alexander.warg@os.inf.tu-dresden.de](mailto:alexander.warg@os.inf.tu-dresden.de)

Definition in file [kip](#).

## 16.528 kip

[Go to the documentation of this file.](#)

```

00001 // vim:set ft=cpp: -*- Mode: C++ -*-
00010 /*
00011  * (c) 2008-2009 Author(s)
00012  *     economic rights: Technische Universität Dresden (Germany)
00013  *
00014  * License: see LICENSE.spdx (in this directory or the directories above)
00015  */
00016 #pragma once
00017
00018 #include <l4/cxx/static_vector>
00019 #include <l4/sys/kip.h>
00020
00021 /* C++ version of memory descriptors */
00022
00031
00032 namespace L4
00033 {
00034     namespace Kip
00035     {
00042         class Mem_desc
00043         {
00044         public:
00048             enum Mem_type
00049             {
00050                 Undefined      = 0x0,
00051                 Conventional   = 0x1,
00052                 Reserved       = 0x2,
00053                 Dedicated      = 0x3,
00054                 Shared         = 0x4,
00055
00056                 Info           = 0xd,
00057                 Bootloader     = 0xe,
00058                 Arch           = 0xf
00059             };
00060
00064             enum Info_sub_type
00065             {
00066                 Info_acpi_rsdp = 0,
00067
00068                 Reserved_kernel = 0,
00069                 Reserved_heap   = 1,
00070                 Reserved_mmio   = 2,

```

```

00071     };
00072
00076     enum Arch_sub_type_common
00077     {
00078         Arch_acpi_tables = 3,
00079         Arch_acpi_nvs    = 4,
00080     };
00081
00082 private:
00083     unsigned long _l, _h;
00084
00085 public:
00093     static Mem_desc *first(l4_kernel_info_t *kip) noexcept
00094     {
00095         return reinterpret_cast<Mem_desc *>(reinterpret_cast<char *>(kip) + kip->mem_descs);
00096     }
00097
00098     static Mem_desc const *first(l4_kernel_info_t const *kip) noexcept
00099     {
00100         char const *addr = reinterpret_cast<char const *>(kip) + kip->mem_descs;
00101         return reinterpret_cast<Mem_desc const *>(addr);
00102     }
00103
00111     static unsigned long count(l4_kernel_info_t const *kip) noexcept
00112     {
00113         return kip->mem_descs_num;
00114     }
00115
00122     static void count(l4_kernel_info_t *kip, unsigned count) noexcept
00123     {
00124         kip->mem_descs_num = count;
00125     }
00126
00132     static inline cxx::static_vector<Mem_desc const> all(l4_kernel_info_t const *kip)
00133     {
00134         return cxx::static_vector<Mem_desc const>(Mem_desc::first(kip),
00135                                                    Mem_desc::count(kip));
00136     }
00137
00143     static inline cxx::static_vector<Mem_desc> all(l4_kernel_info_t *kip)
00144     {
00145         return cxx::static_vector<Mem_desc>(Mem_desc::first(kip),
00146                                              Mem_desc::count(kip));
00147     }
00148
00162     Mem_desc(unsigned long start, unsigned long end,
00163              Mem_type t, unsigned char st = 0, bool virt = false,
00164              bool eager = false) noexcept
00165     : _l((start & ~0x3ffUL) | (t & 0x0f) | ((st << 4) & 0x0f0)
00166         | (virt ? 0x0200 : 0x0) | (eager ? 0x100 : 0x0)), _h(end | 0x3ffUL)
00167     {}
00168
00174     unsigned long start() const noexcept { return _l & ~0x3ffUL; }
00175
00181     unsigned long end() const noexcept { return _h | 0x3ffUL; }
00182
00188     unsigned long size() const noexcept { return end() + 1 - start(); }
00189
00195     Mem_type type() const noexcept
00196     {
00197         return static_cast<Mem_type>(_l & 0x0f);
00198     }
00199
00205     unsigned char sub_type() const noexcept { return (_l >> 4) & 0x0f; }
00206
00213     unsigned is_virtual() const noexcept { return _l & 0x200; }
00214
00219     unsigned eager_map() const noexcept { return _l & 0x100; }
00220
00233     void set(unsigned long start, unsigned long end,
00234             Mem_type t, unsigned char st = 0, bool virt = false,
00235             bool eager = false) noexcept
00236     {
00237         _l = (start & ~0x3ffUL) | (t & 0x0f) | ((st << 4) & 0x0f0)
00238             | (virt ? 0x0200 : 0x0) | (eager ? 0x0100 : 0x0);
00239
00240         _h = end | 0x3ffUL;
00241     }
00242
00243 };
00244 };
00245 };

```



## 16.529 kobject

```

00001 // vi:set ft=c++: -*- Mode: C++ -*-
00002 /* \file
00003  * Kobject C++ interface.
00004  */
00005 /*
00006  * Copyright (C) 2015-2017, 2019, 2021, 2023-2024 Kernkonzept GmbH.
00007  * Author(s): Alexander Warg <alexander.warg@kernkonzept.com>
00008  *
00009  * License: see LICENSE.spdx (in this directory or the directories above)
00010  */
00011 #pragma once
00012
00013 #include "kernel_object.h"
00014 #include "types.h"
00015 #include "__typeinfo.h"
00016
00017 namespace L4 {
00018
00036 class L4_EXPORT Kobject
00037 {
00038 private:
00039     Kobject();
00040     Kobject(Kobject const &);
00041     Kobject &operator = (Kobject const &);
00042
00043     template<typename T> friend struct Kobject_typeid;
00044
00045 protected:
00046     typedef Typeid::Iface<L4_PROTO_META, Kobject> __Iface;
00047     typedef Typeid::Iface_list<__Iface> __Iface_list;
00048
00055     struct __Kobject_typeid
00056     {
00057         typedef Type_info::Demand_t<> Demand;
00058         static Type_info const _m;
00059     };
00060
00069     l4_cap_idx_t cap() const noexcept { return _c(); }
00070
00071 private:
00072
00077     l4_cap_idx_t _c() const noexcept
00078     { return reinterpret_cast<l4_cap_idx_t>(this) & L4_CAP_MASK; }
00079
00080 public:
00100     l4_msgtag_t dec_refcnt(l4_mword_t diff, l4_utcb_t *utcb = l4_utcb())
00101     { return l4_kobject_dec_refcnt_u(cap(), diff, utcb); }
00102 };
00103
00104 template<typename Derived, l4_proto_t PROTO = L4::PROTO_ANY,
00105         typename S_DEMAND = Type_info::Demand_t<> >
00106 struct Kobject_0t : Kobject_t<Derived, L4::Kobject, PROTO, S_DEMAND> {};
00107
00108 }
00109

```

## 16.530 l4/sys/ktrace.h File Reference


L4 kernel event tracing.

```

#include <l4/sys/types.h>
#include <l4/sys/ktrace_events.h>
#include <l4/sys/__ktrace-impl.h>

```

Include dependency graph for `ktrace.h`:



## Functions

- `l4_umword_t fiasco_tbuf_log` (const char \*text)  
Create new trace-buffer entry with describing <text>.
- `l4_umword_t fiasco_tbuf_log_3val` (const char \*text, `l4_umword_t` v1, `l4_umword_t` v2, `l4_umword_t` v3)  
Create new trace-buffer entry with describing <text> and three additional values.
- `l4_umword_t fiasco_tbuf_log_binary` (const unsigned char \*data)  
Create new trace-buffer entry with binary data.
- void `fiasco_tbuf_clear` (void)  
Clear trace-buffer.
- void `fiasco_tbuf_dump` (void)  
Dump trace-buffer to kernel console.

## 16.530.1 Detailed Description

[L4](#) kernel event tracing.

Definition in file [ktrace.h](#).

## 16.531 ktrace.h

[Go to the documentation of this file.](#)

```

00001
00006 /*
00007  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00008  *          Björn Döbel <doebel@os.inf.tu-dresden.de>,
00009  *          Torsten Frenzel <frenzel@os.inf.tu-dresden.de>
00010  *          2015 Adam Lackorzynski <adam@l4re.org>
00011  *          economic rights: Technische Universität Dresden (Germany)
00012  *
00013  * License: see LICENSE.spdx (in this directory or the directories above)
00014  */
00015 /*****
00016 #ifndef __L4_KTRACE_H__
00017 #define __L4_KTRACE_H__
00018
00019 #include <l4/sys/types.h>
00020 #include <l4/sys/ktrace_events.h>
00021
00033
00041 L4_INLINE l4_umword_t
00042 fiasco_tbuf_log(const char *text);
00043
00055 L4_INLINE l4_umword_t
00056 fiasco_tbuf_log_3val(const char *text, l4_umword_t v1, l4_umword_t v2, l4_umword_t v3);
00057
00065 L4_INLINE l4_umword_t
00066 fiasco_tbuf_log_binary(const unsigned char *data);
00067
00072 L4_INLINE void
00073 fiasco_tbuf_clear(void);
00074
00079 L4_INLINE void
00080 fiasco_tbuf_dump(void);
00081
00082 #include <l4/sys/__ktrace-impl.h>
00083
00084 #endif

```

## 16.532 amd64/l4/sys/arch/l4int.h File Reference

Fixed sized integer types, AMD64 version.

### Macros

- `#define L4_MWORD_BITS 64`  
*Size of machine words in bits.*

### Typedefs

- `typedef unsigned long l4_size_t`  
*Unsigned size type.*
- `typedef signed long l4_ssize_t`  
*Signed size type.*

### 16.532.1 Detailed Description

Fixed sized integer types, AMD64 version.

Definition in file [l4int.h](#).

## 16.533 I4int.h

[Go to the documentation of this file.](#)

```

00001 /*****
00007 */
00008 * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00009 *      Alexander Warg <warg@os.inf.tu-dresden.de>
00010 *      economic rights: Technische Universität Dresden (Germany)
00011 *
00012 * License: see LICENSE.spdx (in this directory or the directories above)
00013 */
00014 #pragma once
00015
00020
00021 #define L4_MWORD_BITS          64
00022
00023 typedef unsigned long          l4_size_t;
00024 typedef signed long           l4_ssize_t;
00026

```

## 16.534 arm/l4/sys/arch/l4int.h File Reference

Fixed sized integer types, arm version.

### Macros

- `#define L4_MWORD_BITS 32`  
*Size of machine words in bits.*

### Typedefs

- `typedef unsigned int l4_size_t`  
*Unsigned size type.*
- `typedef signed int l4_ssize_t`  
*Signed size type.*

### 16.534.1 Detailed Description

Fixed sized integer types, arm version.

Definition in file [l4int.h](#).

## 16.535 I4int.h

[Go to the documentation of this file.](#)

```

00001
00006 /*
00007 * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00008 *      Alexander Warg <warg@os.inf.tu-dresden.de>
00009 *      economic rights: Technische Universität Dresden (Germany)
00010 *
00011 * License: see LICENSE.spdx (in this directory or the directories above)
00012 */
00013 #pragma once
00014
00019
00020 #define L4_MWORD_BITS          32
00021
00022 typedef unsigned int          l4_size_t;
00023 typedef signed int           l4_ssize_t;
00025

```

## 16.536 arm64/l4/sys/arch/l4int.h File Reference

Fixed sized integer types, arm version.

### Macros

- `#define L4_MWORD_BITS 64`  
*Size of machine words in bits.*

### Typedefs

- `typedef unsigned long l4_size_t`  
*Unsigned size type.*
- `typedef signed long l4_ssize_t`  
*Signed size type.*

### 16.536.1 Detailed Description

Fixed sized integer types, arm version.

Definition in file [l4int.h](#).

## 16.537 l4int.h

[Go to the documentation of this file.](#)


```
00001
00006 /*
00007  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00008  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00009  *      economic rights: Technische Universität Dresden (Germany)
00010  *
00011  * License: see LICENSE.spdx (in this directory or the directories above)
00012  */
00013 #pragma once
00014
00019
00020 #define L4_MWORD_BITS      64
00021
00022 typedef unsigned long      l4_size_t;
00023 typedef signed long       l4_ssize_t;
00025
```

## 16.538 l4/sys/l4int.h File Reference


Fixed sized integer types, generic version.

```
#include <l4/sys/arch/l4int.h>
```

Include dependency graph for l4int.h:



This graph shows which files directly or indirectly include this file:



### Typedefs

- typedef signed char **l4\_int8\_t**  
*Signed 8bit value.*
- typedef unsigned char **l4\_uint8\_t**  
*Unsigned 8bit value.*
- typedef signed short int **l4\_int16\_t**  
*Signed 16bit value.*
- typedef unsigned short int **l4\_uint16\_t**  
*Unsigned 16bit value.*
- typedef signed int **l4\_int32\_t**  
*Signed 32bit value.*
- typedef unsigned int **l4\_uint32\_t**  
*Unsigned 32bit value.*
- typedef signed long long **l4\_int64\_t**  
*Signed 64bit value.*
- typedef unsigned long long **l4\_uint64\_t**  
*Unsigned 64bit value.*
- typedef unsigned long **l4\_addr\_t**  
*Address type.*
- typedef signed long **l4\_mword\_t**  
*Signed machine word.*
- typedef unsigned long **l4\_umword\_t**

*Unsigned machine word.*

- typedef [l4\\_uint64\\_t](#) [l4\\_cpu\\_time\\_t](#)

*CPU clock type.*

- typedef [l4\\_uint64\\_t](#) [l4\\_kernel\\_clock\\_t](#)

*Kernel clock type.*

## 16.538.1 Detailed Description

Fixed sized integer types, generic version.

Definition in file [l4int.h](#).

## 16.539 l4int.h

[Go to the documentation of this file.](#)

```

00001
00007
00013 /*
00014  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00015  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00016  *      economic rights: Technische Universität Dresden (Germany)
00017  *
00018  * License: see LICENSE.spdx (in this directory or the directories above)
00019  */
00020 #ifndef __L4_SYS_L4INT_H__
00021 #define __L4_SYS_L4INT_H__
00022
00023 /* fixed sized data types */
00024 typedef signed char      l4_int8_t;
00025 typedef unsigned char    l4_uint8_t;
00026 typedef signed short int l4_int16_t;
00027 typedef unsigned short int l4_uint16_t;
00028 typedef signed int       l4_int32_t;
00029 typedef unsigned int     l4_uint32_t;
00030 typedef signed long long l4_int64_t;
00031 typedef unsigned long long l4_uint64_t;
00032
00033 /* some common data types */
00034 typedef unsigned long    l4_addr_t;
00035
00036
00037 typedef signed long      l4_mword_t;
00040 typedef unsigned long    l4_umword_t;
00047 typedef l4_uint64_t l4_cpu_time_t;
00048
00053 typedef l4_uint64_t l4_kernel_clock_t;
00054
00055 #include <l4/sys/arch/l4int.h>
00056
00057 #endif /* !__L4_SYS_L4INT_H__ */

```

## 16.540 x86/l4/sys/arch/l4int.h File Reference

Fixed sized integer types, x86 version.

### Macros

- #define [L4\\_MWORD\\_BITS](#) 32

*Size of machine words in bits.*

## Typedefs

- typedef unsigned int **l4\_size\_t**  
*Unsigned size type.*
- typedef signed int **l4\_ssize\_t**  
*Signed size type.*

### 16.540.1 Detailed Description

Fixed sized integer types, x86 version.

Definition in file [l4int.h](#).

## 16.541 l4int.h

[Go to the documentation of this file.](#)

```

00001
00006 /*
00007  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00008  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00009  *      economic rights: Technische Universität Dresden (Germany)
00010  *
00011  * License: see LICENSE.spdx (in this directory or the directories above)
00012  */
00013 #pragma once
00014
00019
00020 #define L4_MWORD_BITS          32
00021
00022 typedef unsigned int          l4_size_t;
00023 typedef signed int            l4_ssize_t;
00025


```

### 16.542 l4/sys/memdesc.h File Reference

Memory description functions.

```
#include <l4/sys/kip.h>
```

Include dependency graph for memdesc.h:





## Data Structures

- struct [l4\\_kernel\\_info\\_mem\\_desc\\_t](#)  
*Memory descriptor data structure.*

## Typedefs

- typedef struct [l4\\_kernel\\_info\\_mem\\_desc\\_t](#) [l4\\_kernel\\_info\\_mem\\_desc\\_t](#)  
*Memory descriptor data structure.*

## Enumerations

- enum [l4\\_mem\\_type\\_t](#) {  
  [l4\\_mem\\_type\\_undefined](#) = 0x0 , [l4\\_mem\\_type\\_conventional](#) = 0x1 , [l4\\_mem\\_type\\_reserved](#) = 0x2 ,  
  [l4\\_mem\\_type\\_dedicated](#) = 0x3 ,  
  [l4\\_mem\\_type\\_shared](#) = 0x4 , [l4\\_mem\\_type\\_info](#) = 0xd , [l4\\_mem\\_type\\_bootloader](#) = 0xe , [l4\\_mem\\_type\\_archspecific](#)  
  = 0xf }  
*Type of a memory descriptor.*
- enum [l4\\_mem\\_info\\_sub\\_type\\_t](#) { [l4\\_mem\\_info\\_acpi\\_rsdp](#) = 0 , [l4\\_mem\\_reserved\\_kernel](#) = 0 ,  
  [l4\\_mem\\_reserved\\_heap](#) = 1 , [l4\\_mem\\_reserved\\_mmio](#) = 2 }  
*Memory sub types for l4\_mem\_type\_info descriptors.*
- enum [l4\\_mem\\_archspecific\\_sub\\_type\\_common\\_t](#) { [l4\\_mem\\_archspecific\\_acpi\\_tables](#) = 3 , [l4\\_mem\\_archspecific\\_acpi\\_nvs](#)  
  = 4 }  
*Memory sub types for l4\_mem\_type\_archspecific descriptors.*

## Functions

- [l4\\_kernel\\_info\\_mem\\_desc\\_t \\* l4\\_kernel\\_info\\_get\\_mem\\_descs](#) ([l4\\_kernel\\_info\\_t](#) \*kip) [L4\\_NOTHROW](#)  
*Get pointer to memory descriptors from KIP.*
- unsigned [l4\\_kernel\\_info\\_get\\_num\\_mem\\_descs](#) ([l4\\_kernel\\_info\\_t](#) \*kip) [L4\\_NOTHROW](#)  
*Get number of memory descriptors in KIP.*
- void [l4\\_kernel\\_info\\_set\\_mem\\_desc](#) ([l4\\_kernel\\_info\\_mem\\_desc\\_t](#) \*md, [l4\\_addr\\_t](#) start, [l4\\_addr\\_t](#) end, unsigned type, unsigned virt, unsigned sub\_type) [L4\\_NOTHROW](#)  
*Populate a memory descriptor.*
- [l4\\_umword\\_t l4\\_kernel\\_info\\_get\\_mem\\_desc\\_start](#) ([l4\\_kernel\\_info\\_mem\\_desc\\_t](#) \*md) [L4\\_NOTHROW](#)  
*Get start address of the region described by the memory descriptor.*
- [l4\\_umword\\_t l4\\_kernel\\_info\\_get\\_mem\\_desc\\_end](#) ([l4\\_kernel\\_info\\_mem\\_desc\\_t](#) \*md) [L4\\_NOTHROW](#)  
*Get end address of the region described by the memory descriptor.*
- [l4\\_umword\\_t l4\\_kernel\\_info\\_get\\_mem\\_desc\\_type](#) ([l4\\_kernel\\_info\\_mem\\_desc\\_t](#) \*md) [L4\\_NOTHROW](#)  
*Get type of the memory region.*
- [l4\\_umword\\_t l4\\_kernel\\_info\\_get\\_mem\\_desc\\_subtype](#) ([l4\\_kernel\\_info\\_mem\\_desc\\_t](#) \*md) [L4\\_NOTHROW](#)  
*Get sub-type of memory region.*
- [l4\\_umword\\_t l4\\_kernel\\_info\\_get\\_mem\\_desc\\_is\\_virtual](#) ([l4\\_kernel\\_info\\_mem\\_desc\\_t](#) \*md) [L4\\_NOTHROW](#)  
*Get virtual flag of the memory descriptor.*

### 16.542.1 Detailed Description

Memory description functions.

Definition in file [memdesc.h](#).

## 16.543 memdesc.h

[Go to the documentation of this file.](#)

```

00001
00006 /*
00007  * (c) 2007-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00008  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00009  *      economic rights: Technische Universität Dresden (Germany)
00010  *
00011  * License: see LICENSE.spdx (in this directory or the directories above)
00012  */
00013 #ifndef __L4SYS__MEMDESC_H__
00014 #define __L4SYS__MEMDESC_H__
00015
00016 #include <l4/sys/kip.h>
00017
00028
00033 enum l4_mem_type_t
00034 {
00035     l4_mem_type_undefined    = 0x0,
00036     l4_mem_type_conventional = 0x1,
00037     l4_mem_type_reserved     = 0x2,
00038     l4_mem_type_dedicated    = 0x3,
00039     l4_mem_type_shared       = 0x4,
00040
00041     l4_mem_type_info         = 0xd,
00042     l4_mem_type_bootloader   = 0xe,
00043     l4_mem_type_archspecific = 0xf,
00044 };
00045
00050 enum l4_mem_info_sub_type_t
00051 {
00052     l4_mem_info_acpi_rsdp = 0,
00053
00054     l4_mem_reserved_kernel = 0,
00055     l4_mem_reserved_heap   = 1,
00056     l4_mem_reserved_mmio   = 2,
00057 };
00058
00063 enum l4_mem_archspecific_sub_type_common_t
00064 {
00065     l4_mem_archspecific_acpi_tables = 3,
00066     l4_mem_archspecific_acpi_nvms   = 4,
00067 };
00068
00069
00077 typedef struct l4_kernel_info_mem_desc_t
00078 {
00080     l4_umword_t l;
00082     l4_umword_t h;
00083 } l4_kernel_info_mem_desc_t;
00084
00085
00090 L4_INLINE
00091 l4_kernel_info_mem_desc_t *
00092 l4_kernel_info_get_mem_descs(l4_kernel_info_t *kip) L4_NOTHROW;
00093
00100 L4_INLINE
00101 unsigned
00102 l4_kernel_info_get_num_mem_descs(l4_kernel_info_t *kip) L4_NOTHROW;
00103
00115 L4_INLINE
00116 void
00117 l4_kernel_info_set_mem_desc(l4_kernel_info_mem_desc_t *md,
00118                             l4_addr_t start,
00119                             l4_addr_t end,
00120                             unsigned type,
00121                             unsigned virt,
00122                             unsigned sub_type) L4_NOTHROW;
00123
00130 L4_INLINE
00131 l4_umword_t
00132 l4_kernel_info_get_mem_desc_start(l4_kernel_info_mem_desc_t *md) L4_NOTHROW;
00133
00140 L4_INLINE
00141 l4_umword_t
00142 l4_kernel_info_get_mem_desc_end(l4_kernel_info_mem_desc_t *md) L4_NOTHROW;
00143
00150 L4_INLINE
00151 l4_umword_t
00152 l4_kernel_info_get_mem_desc_type(l4_kernel_info_mem_desc_t *md) L4_NOTHROW;
00153
00163 L4_INLINE
00164 l4_umword_t
00165 l4_kernel_info_get_mem_desc_subtype(l4_kernel_info_mem_desc_t *md) L4_NOTHROW;

```

```

00166
00173 L4_INLINE
00174 l4_umword_t
00175 l4_kernel_info_get_mem_desc_is_virtual(l4_kernel_info_mem_desc_t *md) L4_NOTHROW;
00176
00177 /*****
00178  * Implementations
00179  *****/
00180
00181 L4_INLINE
00182 l4_kernel_info_mem_desc_t *
00183 l4_kernel_info_get_mem_descs(l4_kernel_info_t *kip) L4_NOTHROW
00184 {
00185     return (l4_kernel_info_mem_desc_t *) ((l4_addr_t)kip + kip->mem_descs);
00186 }
00187
00188 L4_INLINE
00189 unsigned
00190 l4_kernel_info_get_num_mem_descs(l4_kernel_info_t *kip) L4_NOTHROW
00191 {
00192     return kip->mem_descs_num;
00193 }
00194
00195 L4_INLINE
00196 void
00197 l4_kernel_info_set_mem_desc(l4_kernel_info_mem_desc_t *md,
00198                             l4_addr_t start,
00199                             l4_addr_t end,
00200                             unsigned type,
00201                             unsigned virt,
00202                             unsigned sub_type) L4_NOTHROW
00203 {
00204     md->l = (start & ~0x3ffUL) | (type & 0x0f) | ((sub_type < 4) & 0x0f0)
00205           | (virt ? 0x200 : 0x0);
00206     md->h = end;
00207 }
00208
00209
00210 L4_INLINE
00211 l4_umword_t
00212 l4_kernel_info_get_mem_desc_start(l4_kernel_info_mem_desc_t *md) L4_NOTHROW
00213 {
00214     return md->l & ~0x3ffUL;
00215 }
00216
00217 L4_INLINE
00218 l4_umword_t
00219 l4_kernel_info_get_mem_desc_end(l4_kernel_info_mem_desc_t *md) L4_NOTHROW
00220 {
00221     return md->h | 0x3ffUL;
00222 }
00223
00224 L4_INLINE
00225 l4_umword_t
00226 l4_kernel_info_get_mem_desc_type(l4_kernel_info_mem_desc_t *md) L4_NOTHROW
00227 {
00228     return md->l & 0xf;
00229 }
00230
00231 L4_INLINE
00232 l4_umword_t
00233 l4_kernel_info_get_mem_desc_subtype(l4_kernel_info_mem_desc_t *md) L4_NOTHROW
00234 {
00235     return (md->l & 0xf0) >> 4;
00236 }
00237
00238 L4_INLINE
00239 l4_umword_t
00240 l4_kernel_info_get_mem_desc_is_virtual(l4_kernel_info_mem_desc_t *md) L4_NOTHROW
00241 {
00242     return md->l & 0x200;
00243 }
00244
00245 #endif /* ! __L4SYS__MEMDESC_H__ */

```

## 16.544 meta

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00002
00003 #pragma once
00004
00005 #include <l4/sys/meta>
00006 #include <l4/sys/typeinfo_svr>

```

```

00007
00008 namespace L4Re { namespace Util {
00009 using L4::Util::handle_meta_request;
00010 }}

```

## 16.545 I4/sys/meta File Reference


Meta interface for getting dynamic type information about objects behind capabilities.

```


#include "kobject"
#include "cxx/ipc_iface"
#include "cxx/ipc_string"

```

Include dependency graph for meta:



This graph shows which files directly or indirectly include this file:



### Data Structures

- class [L4::Meta](#)

*Meta* interface that shall be implemented by each [L4Re](#) object and gives access to the dynamic type information for [L4Re](#) objects.

## Namespaces

- namespace [L4](#)  
*[L4](#) low-level kernel interface.*

### 16.545.1 Detailed Description

Meta interface for getting dynamic type information about objects behind capabilities.

Definition in file [meta](#).

## 16.546 meta

[Go to the documentation of this file.](#)

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00007 /*
00008  * (c) 2008-2009 Alexander Warg <warg@os.inf.tu-dresden.de>
00009  *      economic rights: Technische Universität Dresden (Germany)
00010  *
00011  * License: see LICENSE.spdx (in this directory or the directories above)
00012  */
00013
00014 #pragma once
00015
00016 #include "kobject"
00017 #include "cxx/ipc_iface"
00018 #include "cxx/ipc_string"
00019
00020 namespace L4 {
00021
00026 class Meta : public Kobject_t<Meta, Kobject, L4_PROTO_META>
00027 {
00028 public:
00035     L4_INLINE_RPC(l4_msgtag_t, num_interfaces, ());
00036
00050     L4_INLINE_RPC(l4_msgtag_t, interface, (l4_umword_t idx, long *proto,
00051                                           L4::Ipc::String<char> *name));
00052
00064     L4_INLINE_RPC(l4_msgtag_t, supports, (l4_mword_t protocol));
00065
00066     typedef L4::Typeid::Rpc<num_interfaces_t, interface_t, supports_t> Rpc;
00067 };
00068
00069 }
```


### 16.547 l4/sys/obj\_info.h File Reference

Debugger related functions.

```

#include <l4/sys/compiler.h>
#include <l4/sys/debugger.h>
```

```
#include <l4/sys/l4int.h>
Include dependency graph for obj_info.h:
```



## Functions

- [l4\\_msgtag\\_t l4\\_debugger\\_query\\_obj\\_infos](#) ([l4\\_cap\\_idx\\_t](#) cap, [l4\\_addr\\_t](#) ku\_mem\_addr, [l4\\_size\\_t](#) ku\_mem\_size, [l4\\_umword\\_t](#) skip, [l4\\_umword\\_t](#) \*result\_cnt, [l4\\_umword\\_t](#) \*result\_all) [L4\\_NOTHROW](#)

Retrieve information from the kernel about all objects in the mapping database and write data to the passed KU memory.

### 16.547.1 Detailed Description

Debugger related functions.

#### Attention

This API is subject to change!

Definition in file [obj\\_info.h](#).

## 16.547.2 Function Documentation

### 16.547.2.1 l4\_debugger\_query\_obj\_infos()

```
l4_msgtag_t l4_debugger_query_obj_infos (
    l4_cap_idx_t cap,
    l4_addr_t ku_mem_addr,
    l4_size_t ku_mem_size,
    l4_umword_t skip,
    l4_umword_t * result_cnt,
    l4_umword_t * result_all) [inline]
```

Retrieve information from the kernel about all objects in the mapping database and write data to the passed KU memory.

#### Parameters

	<i>cap</i>	Capability of the debugger object.
	<i>ku_mem_addr</i>	Address of the KU memory for writing the information.
	<i>ku_mem_size</i>	Size of the KU memory to writing the information.
	<i>skip</i>	Number of objects to skip.
out	<i>result_cnt</i>	Number of objects in the mapping database.
out	<i>result_all</i>	Number of objects written to the KU memory.

#### Note


The kernel will only write a number of object information which fits to the passed KU memory. To retrieve missing object information, repeat the call and adapt the *skip* parameter accordingly.

If this system call is performed several times, the number of kernel objects might have changed in the meantime.

Definition at line 177 of file [obj\\_info.h](#).

References [L4\\_NOTHROW](#), and [l4\\_utcb\(\)](#).

Here is the call graph for this function:



## 16.548 obj\_info.h

[Go to the documentation of this file.](#)

```

00001 /*
00002  * Copyright (C) 2023, 2025 Kernkonzept GmbH.
00003  * Author(s): Frank Mehnert <frank.mehnert@kernkonzept.com>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007
00014
00015 #pragma once
00016
00017 #include <l4/sys/compiler.h>
00018 #include <l4/sys/debugger.h>
00019 #include <l4/sys/l4int.h>
00020
00021 struct L4_kobj_info
00022 {
00023     // Type_mapping: See Jdb_mapdb::info_obj_mapping().
00024     struct Mapping
00025     {
00026         enum { Type = 0 };
00027         l4_uint64_t mapping_ptr;
00028         char space_name[16];
00029         l4_uint32_t cap_idx;
00030         l4_uint16_t entry_rights;
00031         l4_uint16_t entry_flags;
00032         l4_uint64_t entry_ptr;
00033     };
00034
00035     // Type_thread: See Jdb_tcb::info_kobject().
00036     struct Thread
00037     {
00038         enum { Type = 1 };
00039         bool is_kernel;
00040         bool is_current;
00041         bool in_ready_list;
00042         bool is_kernel_task;
00043         l4_uint32_t home_cpu;
00044         l4_uint32_t current_cpu;
00045         l4_int64_t ref_cnt;
00046         l4_uint64_t space_id;
00047     };
00048
00049     // Type_space: See Jdb_space::info_kobject().
00050     struct Space
00051     {
00052         enum { Type = 2 };
00053         bool is_kernel;
00054         l4_int64_t ref_cnt;
00055     };
00056
00057     // Type_vm: See Jdb_vm::info_kobject().
00058     struct Vm
00059     {
00060         enum { Type = 3 };
00061         l4_uint64_t utcb;
00062         l4_uint64_t pc;
00063     };
00064
00065     // Type_ipc_gate: See Jdb_ipc_gate::info_kobject().
00066     struct Ipc_gate
00067     {
00068         enum { Type = 4 };
00069         l4_uint64_t label;
00070         l4_uint64_t thread_id;
00071     };
00072
00073     // Type_irq: See Jdb_kobject_irq::info_kobject().
00074     struct Irq_sender
00075     {
00076         enum { Type = 5 };
00077         char chip_type[10];
00078         l4_uint16_t flags;
00079         l4_uint32_t pin;
00080         l4_uint64_t label;
00081         l4_uint64_t target_id;
00082         l4_int64_t queued;
00083     };
00084
00085     // Type_irq: See Jdb_kobject_irq::info_kobject().
00086     struct Irq_semaphore
00087     {
00088         enum { Type = 6 };

```



```

00089     char chip_type[10];
00090     l4_uint16_t flags;
00091     l4_uint32_t pin;
00092     l4_uint64_t sender_id;
00093     l4_uint64_t target_id;
00094     l4_int64_t queued;
00095 };
00096
00097 // Type_factory: See Jdb_factory::info_kobject().
00098 struct Factory
00099 {
00100     enum { Type = 7 };
00101     l4_uint64_t current;
00102     l4_uint64_t limit;
00103 };
00104
00105 struct Jdb          { enum { Type = 8 }; };
00106 struct Scheduler    { enum { Type = 9 }; };
00107 struct Vlog         { enum { Type = 10 }; };
00108 struct Pfc          { enum { Type = 11 }; };
00109 struct Dmar_space   { enum { Type = 12 }; };
00110 struct Iommu        { enum { Type = 13 }; };
00111 struct Smmu         { enum { Type = 14 }; };
00112
00113 l4_uint64_t type;
00114 l4_uint64_t id;
00115 l4_uint64_t mapping_ptr;
00116 l4_uint64_t ref_cnt;
00117 union
00118 {
00119     Thread thread;
00120     Space space;
00121     Vm vm;
00122     Ipc_gate ipc_gate;
00123     Irq_sender irq_sender;
00124     Irq_semaphore irq_semaphore;
00125     Factory factory;
00126     Mapping mapping;
00127     l4_uint64_t raw[5];
00128 };
00129 };
00130
00131 static_assert(sizeof(L4_kobj_info) == 64, "Size of Jobj_info");
00132
00151 L4_INLINE l4_msgtag_t
00152 l4_debugger_query_obj_infos(l4_cap_idx_t cap, l4_addr_t ku_mem_addr,
00153                             l4_size_t ku_mem_size, l4_umword_t skip,
00154                             l4_umword_t *result_cnt, l4_umword_t *result_all)
00155     L4_NOTHROW;
00156
00157 L4_INLINE l4_msgtag_t
00158 l4_debugger_query_obj_infos_u(l4_cap_idx_t cap, l4_addr_t ku_mem_addr,
00159                               l4_size_t ku_mem_size, l4_umword_t skip,
00160                               l4_umword_t *result_cnt, l4_umword_t *result_all,
00161                               l4_utcb_t *utcb) L4_NOTHROW
00162 {
00163     l4_utcb_mr()->mr[0] = L4_DEBUGGER_OBJ_INFO_OP;
00164     l4_utcb_mr()->mr[1] = ku_mem_addr;
00165     l4_utcb_mr()->mr[2] = ku_mem_size;
00166     l4_utcb_mr()->mr[3] = skip;
00167
00168     l4_msgtag_t tag = l4_invoke_debugger(cap, l4_msgtag(0, 4, 0, 0), utcb);
00169
00170     *result_cnt = l4_utcb_mr()->mr[0];
00171     *result_all = l4_utcb_mr()->mr[1];
00172
00173     return tag;
00174 }
00175
00176 L4_INLINE l4_msgtag_t
00177 l4_debugger_query_obj_infos(l4_cap_idx_t cap, l4_addr_t ku_mem_addr,
00178                             l4_size_t ku_mem_size, l4_umword_t skip,
00179                             l4_umword_t *result_cnt, l4_umword_t *result_all)
00180     L4_NOTHROW
00181 {
00182     return l4_debugger_query_obj_infos_u(cap, ku_mem_addr, ku_mem_size, skip,
00183                                           result_cnt, result_all, l4_utcb());
00184 }


```

## 16.549 l4/sys/pager File Reference


Pager and lo\_pager C++ interface.

```
#include <l4/sys/capability>
#include <l4/sys/types.h>
#include <l4/sys/cxx/ipc_types>
#include <l4/sys/cxx/ipc_iface>
```

Include dependency graph for pager:



This graph shows which files directly or indirectly include this file:



## Data Structures

- class `L4::lo_pager`  
*lo\_pager* interface.
- class `L4::Pager`  
*Pager* interface including the *lo\_pager* interface.

## Namespaces

- namespace [L4](#)  
*L4 low-level kernel interface.*

### 16.549.1 Detailed Description

Pager and Io\_pager C++ interface.

Definition in file [pager](#).

## 16.550 pager

[Go to the documentation of this file.](#)

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00006 /*
00007  * (c) 2014 Alexander Warg <alexander.warg@kernkonzept.com>
00008  *
00009  * License: see LICENSE.spdx (in this directory or the directories above)
00010  */
00011
00012 #pragma once
00013
00014 #include <l4/sys/capability>
00015 #include <l4/sys/types.h>
00016 #include <l4/sys/cxx/ipc_types>
00017 #include <l4/sys/cxx/ipc_iface>
00018
00019 namespace L4 {
00020
00050 class L4_EXPORT Io_pager :
00051     public Kobject_0t<Io_pager, L4_PROTO_IO_PAGE_FAULT>
00052 {
00053 public:
00069     L4_INLINE_RPC(
00070         l4_msgtag_t, io_page_fault, (l4_fpage_t io_pfa, l4_umword_t pc,
00071                                     L4::Ipc::Rcv_fpage rwin,
00072                                     L4::Ipc::Opt<L4::Ipc::Snd_fpage &> fp));
00073
00074     typedef L4::Typeid::Rpc_nocode<io_page_fault_t> Rpcs;
00075 };
00076
00087 class L4_EXPORT Pager :
00088     public Kobject_t<Pager, Io_pager, L4_PROTO_PAGE_FAULT>
00089 {
00090 public:
00123     L4_INLINE_RPC(
00124         l4_msgtag_t, page_fault, (l4_umword_t pfa, l4_umword_t pc,
00125                                   L4::Ipc::Rcv_fpage rwin,
00126                                   L4::Ipc::Opt<L4::Ipc::Snd_fpage &> fp));
00127
00128     typedef L4::Typeid::Rpc_nocode<page_fault_t> Rpcs;
00129 };
00130
00131 }

```

## 16.551 l4/sys/platform\_control File Reference


Platform control object.

```

#include <l4/sys/capability>
#include <l4/sys/platform_control.h>

```

```
#include <l4/sys/cxx/ipc_iface>
Include dependency graph for platform_control:
```



## Data Structures

- class [L4::Platform\\_control](#)

[L4](#) C++ interface for controlling platform-wide properties, see [Platform Control C API](#) for the C interface.

## Namespaces

- namespace [L4](#)

[L4](#) low-level kernel interface.

### 16.551.1 Detailed Description

Platform control object.

Definition in file [platform\\_control](#).

## 16.552 platform\_control

[Go to the documentation of this file.](#)

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00002 /*
00003  * (c) 2014 Steffen Liebergeld <steffen.liebergeld@kernkonzept.com>
00004  *      Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00005  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00006  *      economic rights: Technische Universität Dresden (Germany)
00007  *
00008  * License: see LICENSE.spdx (in this directory or the directories above)
00009  */
00010
00011 #pragma once
00012
00013 #include <l4/sys/capability>
00014 #include <l4/sys/platform_control.h>
00015 #include <l4/sys/cxx/ipc_iface>
00016
00017 namespace L4 {
00018
00019 class L4_EXPORT Platform_control
00020 : public Kobject_t<Platform_control, Kobject, L4_PROTO_PLATFORM_CTL>
00021 {
00022 public:
00023     L4_INLINE_RPC_OP(L4_PLATFORM_CTL_SYS_SUSPEND_OP,
00024                     l4_msgtag_t, system_suspend, (l4_umword_t extras));
00025
00026     L4_INLINE_RPC_OP(L4_PLATFORM_CTL_SYS_SHUTDOWN_OP,
00027                     l4_msgtag_t, system_shutdown, (l4_umword_t reboot));
00028
00029     L4_INLINE_RPC_OP(L4_PLATFORM_CTL_CPU_ALLOW_SHUTDOWN_OP,
00030                     l4_msgtag_t, cpu_allow_shutdown,
00031                     (l4_umword_t phys_id, l4_umword_t enable));
00032
00033     L4_INLINE_RPC_OP(L4_PLATFORM_CTL_CPU_ENABLE_OP,
00034                     l4_msgtag_t, cpu_enable, (l4_umword_t phys_id));
00035
00036     L4_INLINE_RPC_OP(L4_PLATFORM_CTL_CPU_DISABLE_OP,
00037                     l4_msgtag_t, cpu_disable, (l4_umword_t phys_id));
00038
00039     typedef L4::Typeid::Rpcsys<system_suspend_t, system_shutdown_t,
00040                               cpu_allow_shutdown_t, cpu_enable_t,
00041                               cpu_disable_t> Rpcsys;
00042 };
00043
00044 }
00045
00046
00047
00048

```

## 16.553 platform\_control.h

```

00001 /*
00002  * Copyright (C) 2026 Kernkonzept GmbH.
00003  * Author(s): Jan Klötzke <jan.kloetzke@kernkonzept.com>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007 #pragma once

```

## 16.554 platform\_control.h

```

00001 /*
00002  * Copyright (C) 2024 Kernkonzept GmbH.
00003  * Author(s): Jan Klötzke <jan.kloetzke@kernkonzept.com>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007 #pragma once
00008
00009 #include <l4/sys/__platform_control-arm.h>

```

## 16.555 platform\_control.h

```

00001 /*
00002  * Copyright (C) 2024 Kernkonzept GmbH.
00003  * Author(s): Jan Klötzke <jan.kloetzke@kernkonzept.com>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007 #pragma once
00008
00009 #include <l4/sys/__platform_control-arm.h>

```

## 16.556 l4/sys/platform\_control.h File Reference


Platform control object.

```


#include <l4/sys/types.h>
#include <l4/sys/utcb.h>
#include <l4/sys/ipc.h>
#include <l4/sys/arch/platform_control.h>

```

Include dependency graph for platform\_control.h:



This graph shows which files directly or indirectly include this file:



## Enumerations

- enum `L4_platform_ctl_ops` {  
`L4_PLATFORM_CTL_SYS_SUSPEND_OP = 0UL` , `L4_PLATFORM_CTL_SYS_SHUTDOWN_OP = 1UL` ,  
`L4_PLATFORM_CTL_CPU_ALLOW_SHUTDOWN_OP = 2UL` , `L4_PLATFORM_CTL_CPU_ENABLE_OP = 3UL` ,  
`L4_PLATFORM_CTL_CPU_DISABLE_OP = 4UL` , `L4_PLATFORM_CTL_SET_TASK_ASID_OP = 0x10UL` }  
*Operations on platform-control objects.*
- enum `L4_platform_ctl_proto` { `L4_PROTO_PLATFORM_CTL = 0` }  
*Predefined protocol type for messages to platform-control objects.*

## Functions

- `l4_msgtag_t l4_platform_ctl_system_suspend (l4_cap_idx_t pfc, l4_umword_t extras) L4_NOTHROW`  
*Enter suspend to RAM.*
- `l4_msgtag_t l4_platform_ctl_system_shutdown (l4_cap_idx_t pfc, l4_umword_t reboot) L4_NOTHROW`  
*Shutdown or reboot the system.*
- `l4_msgtag_t l4_platform_ctl_cpu_allow_shutdown (l4_cap_idx_t pfc, l4_umword_t phys_id, l4_umword_t enable) L4_NOTHROW`  
*Allow a CPU to be shut down.*
- `l4_msgtag_t l4_platform_ctl_cpu_enable (l4_cap_idx_t pfc, l4_umword_t phys_id) L4_NOTHROW`  
*Enable an offline CPU.*
- `l4_msgtag_t l4_platform_ctl_cpu_disable (l4_cap_idx_t pfc, l4_umword_t phys_id) L4_NOTHROW`  
*Disable an online CPU.*

### 16.556.1 Detailed Description

Platform control object.

Definition in file [platform\\_control.h](#).

## 16.557 platform\_control.h

[Go to the documentation of this file.](#)

```

00001
00005 /*
00006  * (c) 2014 Alexander Warg <alexander.warg@kernkonzept.com>
00007  *
00008  * License: see LICENSE.spdx (in this directory or the directories above)
00009  */
00010
00011 #pragma once
00012
00013 #include <l4/sys/types.h>
00014 #include <l4/sys/utcb.h>
00015
00030
00031
00049 L4_INLINE l4_msgtag_t
00050 l4_platform_ctl_system_suspend(l4_cap_idx_t pfc,
00051                               l4_umword_t extras) L4_NOTHROW;
00052
00056 L4_INLINE l4_msgtag_t
00057 l4_platform_ctl_system_suspend_u(l4_cap_idx_t pfc,
00058                                 l4_umword_t extras,
00059                                 l4_utcb_t *utcb) L4_NOTHROW;
00060
00061
00070 L4_INLINE l4_msgtag_t

```

```

00071 l4_platform_ctl_system_shutdown(l4_cap_idx_t pfc,
00072                                l4_umword_t reboot) L4_NOTHROW;
00073
00077 L4_INLINE l4_msgtag_t
00078 l4_platform_ctl_system_shutdown_u(l4_cap_idx_t pfc,
00079                                   l4_umword_t reboot,
00080                                   l4_utcb_t *utcb) L4_NOTHROW;
00081
00091 L4_INLINE l4_msgtag_t
00092 l4_platform_ctl_cpu_allow_shutdown(l4_cap_idx_t pfc,
00093                                    l4_umword_t phys_id,
00094                                    l4_umword_t enable) L4_NOTHROW;
00095
00099 L4_INLINE l4_msgtag_t
00100 l4_platform_ctl_cpu_allow_shutdown_u(l4_cap_idx_t pfc,
00101                                     l4_umword_t phys_id,
00102                                     l4_umword_t enable,
00103                                     l4_utcb_t *utcb) L4_NOTHROW;
00104
00114 L4_INLINE l4_msgtag_t
00115 l4_platform_ctl_cpu_enable(l4_cap_idx_t pfc,
00116                            l4_umword_t phys_id) L4_NOTHROW;
00117
00121 L4_INLINE l4_msgtag_t
00122 l4_platform_ctl_cpu_enable_u(l4_cap_idx_t pfc,
00123                              l4_umword_t phys_id,
00124                              l4_utcb_t *utcb) L4_NOTHROW;
00125
00136 L4_INLINE l4_msgtag_t
00137 l4_platform_ctl_cpu_disable(l4_cap_idx_t pfc,
00138                             l4_umword_t phys_id) L4_NOTHROW;
00139
00143 L4_INLINE l4_msgtag_t
00144 l4_platform_ctl_cpu_disable_u(l4_cap_idx_t pfc,
00145                               l4_umword_t phys_id,
00146                               l4_utcb_t *utcb) L4_NOTHROW;
00147 /* ends l4_platform_control_api group */
00148
00150
00159 enum L4_platform_ctl_ops
00160 {
00161     L4_PLATFORM_CTL_SYS_SUSPEND_OP      = 0UL,
00162     L4_PLATFORM_CTL_SYS_SHUTDOWN_OP     = 1UL,
00163     L4_PLATFORM_CTL_CPU_ALLOW_SHUTDOWN_OP = 2UL,
00164     L4_PLATFORM_CTL_CPU_ENABLE_OP       = 3UL,
00165     L4_PLATFORM_CTL_CPU_DISABLE_OP      = 4UL,
00166
00167     L4_PLATFORM_CTL_SET_TASK_ASID_OP     = 0x10UL,
00168 };
00169
00174 enum L4_platform_ctl_proto
00175 {
00181     L4_PROTO_PLATFORM_CTL = 0
00182 };
00183
00184 /* IMPLEMENTATION -----*/
00185
00186 #include <l4/sys/ipc.h>
00187
00188 L4_INLINE l4_msgtag_t
00189 l4_platform_ctl_system_suspend_u(l4_cap_idx_t pfc,
00190                                  l4_umword_t extras,
00191                                  l4_utcb_t *utcb) L4_NOTHROW
00192 {
00193     l4_msg_regs_t *v = l4_utcb_mr_u(utcb);
00194     v->mr[0] = L4_PLATFORM_CTL_SYS_SUSPEND_OP;
00195     v->mr[1] = extras;
00196     return l4_ipc_call(pfc, utcb, l4_msgtag(L4_PROTO_PLATFORM_CTL, 2, 0, 0),
00197                       L4_IPC_NEVER);
00198 }
00199
00200 L4_INLINE l4_msgtag_t
00201 l4_platform_ctl_system_shutdown_u(l4_cap_idx_t pfc,
00202                                   l4_umword_t reboot,
00203                                   l4_utcb_t *utcb) L4_NOTHROW
00204 {
00205     l4_msg_regs_t *v = l4_utcb_mr_u(utcb);
00206     v->mr[0] = L4_PLATFORM_CTL_SYS_SHUTDOWN_OP;
00207     v->mr[1] = reboot;
00208     return l4_ipc_call(pfc, utcb, l4_msgtag(L4_PROTO_PLATFORM_CTL, 2, 0, 0),
00209                       L4_IPC_NEVER);
00210 }
00211
00212
00213 L4_INLINE l4_msgtag_t
00214 l4_platform_ctl_system_suspend(l4_cap_idx_t pfc,
00215                                l4_umword_t extras) L4_NOTHROW
00216 {

```



```

00217     return l4_platform_ctl_system_suspend_u(pfc, extras, l4_utcb());
00218 }
00219
00220 L4_INLINE l4_msgtag_t
00221 l4_platform_ctl_system_shutdown(l4_cap_idx_t pfc,
00222                                l4_umword_t reboot) L4_NOTHROW
00223 {
00224     return l4_platform_ctl_system_shutdown_u(pfc, reboot, l4_utcb());
00225 }
00226
00227 L4_INLINE l4_msgtag_t
00228 l4_platform_ctl_cpu_allow_shutdown_u(l4_cap_idx_t pfc,
00229                                     l4_umword_t phys_id,
00230                                     l4_umword_t enable,
00231                                     l4_utcb_t *utcb) L4_NOTHROW
00232 {
00233     l4_msg_regs_t *v = l4_utcb_mr_u(utcb);
00234     v->mr[0] = L4_PLATFORM_CTL_CPU_ALLOW_SHUTDOWN_OP;
00235     v->mr[1] = phys_id;
00236     v->mr[2] = enable;
00237     return l4_ipc_call(pfc, utcb, l4_msgtag(L4_PROTO_PLATFORM_CTL, 3, 0, 0),
00238                       L4_IPC_NEVER);
00239 }
00240
00241 L4_INLINE l4_msgtag_t
00242 l4_platform_ctl_cpu_allow_shutdown(l4_cap_idx_t pfc,
00243                                   l4_umword_t phys_id,
00244                                   l4_umword_t enable) L4_NOTHROW
00245 {
00246     return l4_platform_ctl_cpu_allow_shutdown_u(pfc, phys_id, enable, l4_utcb());
00247 }
00248
00249 L4_INLINE l4_msgtag_t
00250 l4_platform_ctl_cpu_enable_u(l4_cap_idx_t pfc,
00251                              l4_umword_t phys_id,
00252                              l4_utcb_t *utcb) L4_NOTHROW
00253 {
00254     l4_msg_regs_t *v = l4_utcb_mr_u(utcb);
00255     v->mr[0] = L4_PLATFORM_CTL_CPU_ENABLE_OP;
00256     v->mr[1] = phys_id;
00257     return l4_ipc_call(pfc, utcb, l4_msgtag(L4_PROTO_PLATFORM_CTL, 2, 0, 0),
00258                       L4_IPC_NEVER);
00259 }
00260
00261 L4_INLINE l4_msgtag_t
00262 l4_platform_ctl_cpu_disable_u(l4_cap_idx_t pfc,
00263                               l4_umword_t phys_id,
00264                               l4_utcb_t *utcb) L4_NOTHROW
00265 {
00266     l4_msg_regs_t *v = l4_utcb_mr_u(utcb);
00267     v->mr[0] = L4_PLATFORM_CTL_CPU_DISABLE_OP;
00268     v->mr[1] = phys_id;
00269     return l4_ipc_call(pfc, utcb, l4_msgtag(L4_PROTO_PLATFORM_CTL, 2, 0, 0),
00270                       L4_IPC_NEVER);
00271 }
00272
00273 L4_INLINE l4_msgtag_t
00274 l4_platform_ctl_cpu_enable(l4_cap_idx_t pfc,
00275                             l4_umword_t phys_id) L4_NOTHROW
00276 {
00277     return l4_platform_ctl_cpu_enable_u(pfc, phys_id, l4_utcb());
00278 }
00279
00280 L4_INLINE l4_msgtag_t
00281 l4_platform_ctl_cpu_disable(l4_cap_idx_t pfc,
00282                              l4_umword_t phys_id) L4_NOTHROW
00283 {
00284     return l4_platform_ctl_cpu_disable_u(pfc, phys_id, l4_utcb());
00285 }
00286
00287 #include <l4/sys/arch/platform_control.h>

```

## 16.558 platform\_control.h

```

00001 /*
00002  * Copyright (C) 2026 Kernkonzept GmbH.
00003  * Author(s): Jan Klötzke <jan.kloetzke@kernkonzept.com>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007 #pragma once

```



## Namespaces

- namespace [L4](#)  
*L4 low-level kernel interface.*

## 16.559.1 Detailed Description

The C++ Receive endpoint interface.

Definition in file [rcv\\_endpoint](#).

## 16.560 rcv\_endpoint

[Go to the documentation of this file.](#)

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00006 /*
00007  * (c) 2017 Alexander Warg <alexander.warg@kernkonzept.com>
00008  *
00009  * License: see LICENSE.spdx (in this directory or the directories above)
00010  */
00011 #pragma once
00012
00013 #include <l4/sys/rcv_endpoint.h>
00014 #include <l4/sys/snd_destination>
00015 #include <l4/sys/types.h>
00016 #include <l4/sys/capability>
00017 #include <l4/sys/cxx/ipc_iface>
00018
00019 namespace L4 {
00020
00021 class Thread;
00022
00030 class L4_EXPORT Rcv_endpoint :
00031     public Kobject_t<Rcv_endpoint, Kobject, L4_PROTO_KOBJECT,
00032         Type_info::Demand_t<1> >
00033 {
00034 public:
00066     L4_INLINE_RPC_OP(L4_RCV_EP_BIND_OP,
00067         l4_msgtag_t, bind_thread, (Ipc::Cap<Thread> t, l4_umword_t label));
00068
00101     l4_msgtag_t bind_snd_destination(Cap<Snd_destination> snd_dst, l4_umword_t label)
00102     {
00103         return l4_rcv_ep_bind_snd_destination(cap(), snd_dst.cap(), label);
00104     }
00105
00106     typedef L4::Typeid::Rpcsys_sys<bind_thread_t> Rpcsys;
00107 };
00108
00109 }
```

## 16.561 l4/sys/rcv\_endpoint.h File Reference


Receive endpoint C interface.

```


#include <l4/sys/utcb.h>
#include <l4/sys/types.h>
```

```
#include <l4/sys/ipc.h>
```

Include dependency graph for rcv\_endpoint.h:



This graph shows which files directly or indirectly include this file:



## Enumerations

- enum [L4\\_rcv\\_ep\\_ops](#) { [L4\\_RCV\\_EP\\_BIND\\_OP](#) = 0x10 }
- Receive endpoint operations.*

## Functions

- [l4\\_msgtag\\_t l4\\_rcv\\_ep\\_bind\\_thread](#) ([l4\\_cap\\_idx\\_t](#) ep, [l4\\_cap\\_idx\\_t](#) thread, [l4\\_umword\\_t](#) label)  
*Bind the IPC receive endpoint to a thread.*
- [l4\\_msgtag\\_t l4\\_rcv\\_ep\\_bind\\_snd\\_destination](#) ([l4\\_cap\\_idx\\_t](#) ep, [l4\\_cap\\_idx\\_t](#) snd\_dst, [l4\\_umword\\_t](#) label)  
*Bind the IPC receive endpoint to a send destination (a thread).*

## 16.561.1 Detailed Description

Receive endpoint C interface.

Definition in file [rcv\\_endpoint.h](#).

## 16.561.2 Enumeration Type Documentation

### 16.561.2.1 L4\_rcv\_ep\_ops

enum [L4\\_rcv\\_ep\\_ops](#)

Receive endpoint operations.

#### Enumerator

L4_RCV_EP_BIND_OP	Bind to thread or thread group.
-------------------	---------------------------------

Definition at line 93 of file [rcv\\_endpoint.h](#).

## 16.562 rcv\_endpoint.h

[Go to the documentation of this file.](#)

```

00001
00005 /*
00006  * (c) 2017 Alexander Warg <alexander.warg@kernkonzept.com>
00007  *
00008  * License: see LICENSE.spdx (in this directory or the directories above)
00009  */
00010 #pragma once
00011
00012 #include <l4/sys/utcb.h>
00013 #include <l4/sys/types.h>
00014
00045 L4_INLINE l4_msgtag_t
00046 l4_rcv_ep_bind_thread(l4_cap_idx_t ep, l4_cap_idx_t thread,
00047                      l4_umword_t label);
00048
00076 L4_INLINE l4_msgtag_t
00077 l4_rcv_ep_bind_snd_destination(l4_cap_idx_t ep, l4_cap_idx_t snd_dst,
00078                               l4_umword_t label);
00079
00084 L4_INLINE l4_msgtag_t
00085 l4_rcv_ep_bind_thread_u(l4_cap_idx_t ep, l4_cap_idx_t thread,
00086                        l4_umword_t label, l4_utcb_t *utcb);
00087
00088 L4_INLINE l4_msgtag_t
00089 l4_rcv_ep_bind_snd_destination_u(l4_cap_idx_t ep, l4_cap_idx_t snd_dst,
00090                                 l4_umword_t label, l4_utcb_t *utcb);
00091
00093 enum L4_rcv_ep_ops
00094 {
00095     L4_RCV_EP_BIND_OP      = 0x10,
00096 };
00097
00098 /* IMPLEMENTATION -----*/
00099
00100 #include <l4/sys/ipc.h>
00101
00102 L4_INLINE l4_msgtag_t
00103 l4_rcv_ep_bind_thread_u(l4_cap_idx_t ep,
00104                        l4_cap_idx_t thread, l4_umword_t label,
00105                        l4_utcb_t *utcb)
00106 {
00107     l4_msg_regs_t *m = l4_utcb_mr_u(utcb);

```

```

00108     m->mr[0] = L4_RCV_EP_BIND_OP;
00109     m->mr[1] = label;
00110     m->mr[2] = l4_map_obj_control(0, 0);
00111     m->mr[3] = l4_obj_fpage(thread, 0, L4_CAP_FPAGE_RWS).raw;
00112     return l4_ipc_call(ep, utcb, l4_msgtag(L4_PROTO_KOBJECT, 2, 1, 0),
00113                       L4_IPC_NEVER);
00114 }
00115
00116 L4_INLINE l4_msgtag_t
00117 l4_rcv_ep_bind_snd_destination_u(l4_cap_idx_t ep,
00118                                 l4_cap_idx_t snd_dst, l4_umword_t label,
00119                                 l4_utcb_t *utcb)
00120 {
00121     l4_msg_regs_t *m = l4_utcb_mr_u(utcb);
00122     m->mr[0] = L4_RCV_EP_BIND_OP;
00123     m->mr[1] = label;
00124     m->mr[2] = l4_map_obj_control(0, 0);
00125     m->mr[3] = l4_obj_fpage(snd_dst, 0, L4_CAP_FPAGE_RWS).raw;
00126     return l4_ipc_call(ep, utcb, l4_msgtag(L4_PROTO_KOBJECT, 2, 1, 0),
00127                       L4_IPC_NEVER);
00128 }
00129
00130 L4_INLINE l4_msgtag_t
00131 l4_rcv_ep_bind_thread(l4_cap_idx_t ep, l4_cap_idx_t thread,
00132                      l4_umword_t label)
00133 {
00134     return l4_rcv_ep_bind_thread_u(ep, thread, label, l4_utcb());
00135 }
00136
00137 L4_INLINE l4_msgtag_t
00138 l4_rcv_ep_bind_snd_destination(l4_cap_idx_t ep, l4_cap_idx_t snd_dst,
00139                                l4_umword_t label)
00140 {
00141     return l4_rcv_ep_bind_snd_destination_u(ep, snd_dst, label, l4_utcb());
00142 }

```

## 16.563 l4/sys/scheduler File Reference

Scheduler object functions.

```

#include <l4/sys/icu>
#include <l4/sys/scheduler.h>
#include <l4/sys/capability>
#include <l4/sys/cxx/ipc_iface>

```



```

00011  * License: see LICENSE.spdx (in this directory or the directories above)
00012  */
00013  #pragma once
00014
00015  #include <l4/sys/icu>
00016  #include <l4/sys/scheduler.h>
00017  #include <l4/sys/capability>
00018  #include <l4/sys/cxx/ipc_iface>
00019
00020  namespace L4 {
00021
00046  class L4_EXPORT Scheduler :
00047      public Kobject_t<Scheduler, Icu, L4_PROTO_SCHEDULER,
00048          Type_info::Demand_t<1> >
00049  {
00050  public:
00051      // ABI function for 'info' call
00052      L4_INLINE_RPC_NF_OP(L4_SCHEDULER_INFO_OP,
00053          l4_msgtag_t, info, (l4_umword_t gran_offset, l4_umword_t *map,
00054              l4_umword_t *cpu_max, l4_umword_t *sched_classes));
00055
00074      l4_msgtag_t info(l4_umword_t *cpu_max, l4_sched_cpu_set_t *cpus,
00075          l4_umword_t *sched_classes = nullptr,
00076          l4_utcb_t *utcb = l4_utcb()) const noexcept
00077      {
00078          l4_umword_t max = 0;
00079          l4_umword_t sc = 0;
00080          l4_msgtag_t t =
00081              info_t::call(c(), cpus->gran_offset, &cpus->map, &max, &sc, utcb);
00082          if (cpu_max)
00083              *cpu_max = max;
00084          if (sched_classes)
00085              *sched_classes = sc;
00086          return t;
00087      }
00088
00112      L4_INLINE_RPC_OP(L4_SCHEDULER_RUN_THREAD_OP,
00113          l4_msgtag_t, run_thread, (Ipc::Cap<Thread> thread, l4_sched_param_t const &sp));
00114
00141      L4_INLINE_RPC_OP(L4_SCHEDULER_IDLE_TIME_OP,
00142          l4_msgtag_t, idle_time, (l4_sched_cpu_set_t const &cpus,
00143              l4_kernel_clock_t *us));
00144
00154      bool is_online(l4_umword_t cpu, l4_utcb_t *utcb = l4_utcb()) const noexcept
00155      { return l4_scheduler_is_online_u(cap(), cpu, utcb); }
00156
00157      typedef L4::Typeid::Rpcsys<info_t, run_thread_t, idle_time_t> Rpcsys;
00158  };
00159  }

```

## 16.565 l4/sys/scheduler.h File Reference

Scheduler object functions.


```

#include <l4/sys/kernel_object.h>
#include <l4/sys/ipc.h>


```



Include dependency graph for scheduler.h:



This graph shows which files directly or indirectly include this file:



## Data Structures

- struct [l4\\_sched\\_cpu\\_set\\_t](#)  
*CPU sets.*
- struct [l4\\_sched\\_param\\_t](#)  
*Scheduler parameter set.*

## Typedefs

- typedef struct l4\_sched\_cpu\_set\_t **l4\_sched\_cpu\_set\_t**  
*CPU sets.*
- typedef struct l4\_sched\_param\_t **l4\_sched\_param\_t**  
*Scheduler parameter set.*

## Enumerations

- enum **L4\_scheduler\_classes** { **L4\_SCHEDULER\_CLASS\_FIXED\_PRIO** = 1UL << 1, **L4\_SCHEDULER\_CLASS\_WFQ** = 1UL << 2 }  
*Supported scheduler classes.*
- enum **L4\_scheduler\_ops** { **L4\_SCHEDULER\_INFO\_OP** = 0UL, **L4\_SCHEDULER\_RUN\_THREAD\_OP** = 1UL, **L4\_SCHEDULER\_IDLE\_TIME\_OP** = 2UL }  
*Operations on the Scheduler object.*

## Functions

- **l4\_sched\_cpu\_set\_t l4\_sched\_cpu\_set** (**l4\_umword\_t** offset, unsigned char granularity, **l4\_umword\_t** map=1) **L4\_NOTHROW**
- **l4\_msgtag\_t l4\_scheduler\_info** (**l4\_cap\_idx\_t** scheduler, **l4\_umword\_t** \*cpu\_max, **l4\_sched\_cpu\_set\_t** \*cpus) **L4\_NOTHROW**)  
*Get scheduler information.*
- **l4\_msgtag\_t l4\_scheduler\_info\_with\_classes** (**l4\_cap\_idx\_t** scheduler, **l4\_umword\_t** \*cpu\_max, **l4\_sched\_cpu\_set\_t** \*cpus, **l4\_umword\_t** \*sched\_classes) **L4\_NOTHROW**)  
*Get scheduler information.*
- **l4\_sched\_param\_t l4\_sched\_param** (unsigned prio, **l4\_umword\_t** quantum=0) **L4\_NOTHROW**  
*Construct scheduler parameter.*
- **l4\_msgtag\_t l4\_scheduler\_run\_thread** (**l4\_cap\_idx\_t** scheduler, **l4\_cap\_idx\_t** thread, **l4\_sched\_param\_t** const \*sp) **L4\_NOTHROW**)  
*Run a thread on a Scheduler.*
- **l4\_msgtag\_t l4\_scheduler\_idle\_time** (**l4\_cap\_idx\_t** scheduler, **l4\_sched\_cpu\_set\_t** const \*cpus, **l4\_kernel\_clock\_t** \*us) **L4\_NOTHROW**)  
*Query the idle time (in  $\mu$ s) of a CPU.*
- int **l4\_scheduler\_is\_online** (**l4\_cap\_idx\_t** scheduler, **l4\_umword\_t** cpu) **L4\_NOTHROW**  
*Query if a CPU is online.*

### 16.565.1 Detailed Description

Scheduler object functions.

Definition in file [scheduler.h](#).

## 16.566 scheduler.h

[Go to the documentation of this file.](#)

```

00001
00005 /*
00006  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00007  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00008  *      economic rights: Technische Universität Dresden (Germany)
00009  *
00010  * License: see LICENSE.spdx (in this directory or the directories above)
00011  */
00012 #pragma once
00013
00014 #include <l4/sys/kernel_object.h>
00015 #include <l4/sys/ipc.h>
00016
00040
00046 enum L4_scheduler_classes
00047 {
00049     L4_SCHEDULER_CLASS_FIXED_PRIO = 1UL < 1,
00051     L4_SCHEDULER_CLASS_WFQ        = 1UL < 2,
00052 };
00053
00058 typedef struct l4_sched_cpu_set_t
00059 {
00072     l4_umword_t gran_offset;
00073
00077     l4_umword_t map;
00078
00079 #ifdef __cplusplus
00081     unsigned char granularity() const { return gran_offset >> 24; }
00083     unsigned offset() const { return gran_offset & 0x00ffffff; }
00090     void set(unsigned char granularity, unsigned offset)
00091     {
00092         gran_offset = (static_cast<l4_umword_t>(granularity) << 24)
00093             | (offset & 0x00ffffff);
00094     }
00095 #endif
00096 } l4_sched_cpu_set_t;
00097
00108 L4_INLINE l4_sched_cpu_set_t
00109 l4_sched_cpu_set(l4_umword_t offset, unsigned char granularity,
00110                 l4_umword_t map L4_DEFAULT_PARAM(1)) L4_NOTHROW;
00111
00128 L4_INLINE l4_msgtag_t
00129 l4_scheduler_info(l4_cap_idx_t scheduler, l4_umword_t *cpu_max,
00130                  l4_sched_cpu_set_t *cpus)
00131     L4_NOTHROW __attribute__((nonnull (3)));
00132
00154 L4_INLINE l4_msgtag_t
00155 l4_scheduler_info_with_classes(l4_cap_idx_t scheduler, l4_umword_t *cpu_max,
00156                               l4_sched_cpu_set_t *cpus,
00157                               l4_umword_t *sched_classes)
00158     L4_NOTHROW __attribute__((nonnull (3)));
00159
00163 L4_INLINE l4_msgtag_t
00164 l4_scheduler_info_u(l4_cap_idx_t scheduler, l4_umword_t *cpu_max,
00165                    l4_sched_cpu_set_t *cpus, l4_umword_t *sched_classes,
00166                    l4_utcb_t *utcb) L4_NOTHROW __attribute__((nonnull (3, 5)));
00167
00168
00173 typedef struct l4_sched_param_t
00174 {
00176     l4_sched_cpu_set_t affinity;
00182     l4_umword_t prio;
00184     l4_umword_t quantum;
00185 } l4_sched_param_t;
00186
00195 L4_INLINE l4_sched_param_t
00196 l4_sched_param(unsigned prio,
00197                l4_umword_t quantum L4_DEFAULT_PARAM(0)) L4_NOTHROW;
00198
00206 L4_INLINE l4_msgtag_t
00207 l4_scheduler_run_thread(l4_cap_idx_t scheduler,
00208                        l4_cap_idx_t thread, l4_sched_param_t const *sp)
00209     L4_NOTHROW __attribute__((nonnull));
00210
00214 L4_INLINE l4_msgtag_t
00215 l4_scheduler_run_thread_u(l4_cap_idx_t scheduler, l4_cap_idx_t thread,
00216                          l4_sched_param_t const *sp, l4_utcb_t *utcb)
00217     L4_NOTHROW __attribute__((nonnull));
00218
00226 L4_INLINE l4_msgtag_t
00227 l4_scheduler_idle_time(l4_cap_idx_t scheduler, l4_sched_cpu_set_t const *cpus,
00228                       l4_kernel_clock_t *us)

```

```

00229             L4_NOTHROW __attribute__((nonnull));
00230
00234 L4_INLINE l4_msgtag_t
00235 l4_scheduler_idle_time_u(l4_cap_idx_t scheduler, l4_sched_cpu_set_t const *cpus,
00236                        l4_kernel_clock_t *us, l4_utcb_t *utcb)
00237             L4_NOTHROW __attribute__((nonnull));
00238
00239
00240
00251 L4_INLINE int
00252 l4_scheduler_is_online(l4_cap_idx_t scheduler, l4_umword_t cpu) L4_NOTHROW;
00253
00257 L4_INLINE int
00258 l4_scheduler_is_online_u(l4_cap_idx_t scheduler, l4_umword_t cpu,
00259                        l4_utcb_t *utcb) L4_NOTHROW __attribute__((nonnull));
00260
00261
00262
00269 enum l4_scheduler_ops
00270 {
00271     L4_SCHEDULER_INFO_OP      = 0UL,
00272     L4_SCHEDULER_RUN_THREAD_OP = 1UL,
00273     L4_SCHEDULER_IDLE_TIME_OP = 2UL,
00274 };
00275
00276 /***** Implementations *****/
00277
00278 L4_INLINE l4_sched_cpu_set_t
00279 l4_sched_cpu_set(l4_umword_t offset, unsigned char granularity,
00280                l4_umword_t map) L4_NOTHROW
00281 {
00282     l4_sched_cpu_set_t cs;
00283     cs.gran_offset = ((l4_umword_t)granularity < 24) | (offset & 0x00ffffff);
00284     cs.map         = map;
00285     return cs;
00286 }
00287
00288 L4_INLINE l4_sched_param_t
00289 l4_sched_param(unsigned prio, l4_umword_t quantum) L4_NOTHROW
00290 {
00291     l4_sched_param_t sp;
00292     sp.prio          = prio;
00293     sp.quantum       = quantum;
00294     sp.affinity      = l4_sched_cpu_set(0, ~0, 1);
00295     return sp;
00296 }
00297
00298
00299 L4_INLINE l4_msgtag_t
00300 l4_scheduler_info_u(l4_cap_idx_t scheduler, l4_umword_t *cpu_max,
00301                   l4_sched_cpu_set_t *cpus, l4_umword_t *sched_classes,
00302                   l4_utcb_t *utcb) L4_NOTHROW
00303 {
00304     l4_msg_regs_t *m = l4_utcb_mr_u(utcb);
00305     l4_msgtag_t res;
00306
00307     m->mr[0] = L4_SCHEDULER_INFO_OP;
00308     m->mr[1] = cpus->gran_offset;
00309
00310     res = l4_ipc_call(scheduler, utcb, l4_msgtag(L4_PROTO_SCHEDULER, 2, 0, 0), L4_IPC_NEVER);
00311
00312     if (l4_msgtag_has_error(res))
00313         return res;
00314
00315     cpus->map = m->mr[0];
00316
00317     if (cpu_max)
00318         *cpu_max = m->mr[1];
00319
00320     if (sched_classes)
00321         *sched_classes = m->mr[2];
00322
00323     return res;
00324 }
00325
00326 L4_INLINE l4_msgtag_t
00327 l4_scheduler_run_thread_u(l4_cap_idx_t scheduler, l4_cap_idx_t thread,
00328                          l4_sched_param_t const *sp, l4_utcb_t *utcb) L4_NOTHROW
00329 {
00330     l4_msg_regs_t *m = l4_utcb_mr_u(utcb);
00331     m->mr[0] = L4_SCHEDULER_RUN_THREAD_OP;
00332     m->mr[1] = sp->affinity.gran_offset;
00333     m->mr[2] = sp->affinity.map;
00334     m->mr[3] = sp->prio;
00335     m->mr[4] = sp->quantum;
00336     m->mr[5] = l4_map_obj_control(0, 0);
00337     m->mr[6] = l4_obj_fpage(thread, 0, L4_CAP_FPAGE_RWS).raw;

```

```


00338
00339     return l4_ipc_call(scheduler, utcb, l4_msgtag(L4_PROTO_SCHEDULER, 5, 1, 0), L4_IPC_NEVER);
00340 }
00341
00342 L4_INLINE l4_msgtag_t
00343 l4_scheduler_idle_time_u(l4_cap_idx_t scheduler, l4_sched_cpu_set_t const *cpus,
00344                         l4_kernel_clock_t *us, l4_utcb_t *utcb) L4_NOTHROW
00345 {
00346     l4_msg_regs_t *v = l4_utcb_mr_u(utcb);
00347     l4_msgtag_t res;
00348
00349     v->mr[0] = L4_SCHEDULER_IDLE_TIME_OP;
00350     v->mr[1] = cpus->gran_offset;
00351     v->mr[2] = cpus->map;
00352
00353     res = l4_ipc_call(scheduler, utcb,
00354                      l4_msgtag(L4_PROTO_SCHEDULER, 3, 0, 0), L4_IPC_NEVER);
00355
00356     if (l4_msgtag_has_error(res))
00357         return res;
00358
00359     *us = v->mr64[l4_utcb_mr64_idx(0)];
00360
00361     return res;
00362 }
00363
00364
00365 L4_INLINE int
00366 l4_scheduler_is_online_u(l4_cap_idx_t scheduler, l4_umword_t cpu,
00367                         l4_utcb_t *utcb) L4_NOTHROW
00368 {
00369     l4_sched_cpu_set_t s;
00370     l4_msgtag_t r;
00371     s.gran_offset = cpu;
00372     r = l4_scheduler_info_u(scheduler, NULL, &s, NULL, utcb);
00373     if (l4_msgtag_has_error(r) || l4_msgtag_label(r) < 0)
00374         return 0;
00375
00376     return s.map & 1;
00377 }
00378
00379
00380 L4_INLINE l4_msgtag_t
00381 l4_scheduler_info(l4_cap_idx_t scheduler, l4_umword_t *cpu_max,
00382                  l4_sched_cpu_set_t *cpus) L4_NOTHROW
00383 {
00384     return l4_scheduler_info_u(scheduler, cpu_max, cpus, NULL, l4_utcb());
00385 }
00386
00387 L4_INLINE l4_msgtag_t
00388 l4_scheduler_info_with_classes(l4_cap_idx_t scheduler, l4_umword_t *cpu_max,
00389                               l4_sched_cpu_set_t *cpus,
00390                               l4_umword_t *sched_classes) L4_NOTHROW
00391 {
00392     return l4_scheduler_info_u(scheduler, cpu_max, cpus, sched_classes, l4_utcb());
00393 }
00394
00395 L4_INLINE l4_msgtag_t
00396 l4_scheduler_run_thread(l4_cap_idx_t scheduler,
00397                        l4_cap_idx_t thread, l4_sched_param_t const *sp) L4_NOTHROW
00398 {
00399     return l4_scheduler_run_thread_u(scheduler, thread, sp, l4_utcb());
00400 }
00401
00402 L4_INLINE l4_msgtag_t
00403 l4_scheduler_idle_time(l4_cap_idx_t scheduler, l4_sched_cpu_set_t const *cpus,
00404                       l4_kernel_clock_t *us) L4_NOTHROW
00405 {
00406     return l4_scheduler_idle_time_u(scheduler, cpus, us, l4_utcb());
00407 }
00408
00409 L4_INLINE int
00410 l4_scheduler_is_online(l4_cap_idx_t scheduler, l4_umword_t cpu) L4_NOTHROW
00411 {
00412     return l4_scheduler_is_online_u(scheduler, cpu, l4_utcb());
00413 }

```


## 16.567 l4/sys/semaphore File Reference

Semaphore class definition.

```
#include <l4/sys/irq>
#include <l4/sys/semaphore.h>
Include dependency graph for semaphore:
```



This graph shows which files directly or indirectly include this file:



## Data Structures

- struct [L4::Semaphore](#)

*C++ Kernel-provided semaphore interface, see [Kernel-provided semaphore](#) for the C interface.*

## Namespaces

- namespace [L4](#)

*[L4](#) low-level kernel interface.*

## 16.567.1 Detailed Description

Semaphore class definition.

Definition in file [semaphore](#).

## 16.568 semaphore

[Go to the documentation of this file.](#)


```
00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00006 /*
00007  * (c) 2015 Alexander Warg <alexander.warg@kernkonzept.com>
00008  *
00009  * License: see LICENSE.spdx (in this directory or the directories above)
00010  */
00011
00012 #pragma once
00013
00014 #include <l4/sys/irq>
00015 #include <l4/sys/semaphore.h>
00016
00017 namespace L4 {
00018
00051 struct Semaphore : Kobject_t<Semaphore, Triggerable, L4_PROTO_SEMAPHORE>
00052 {
00067     l4_msgtag_t up(l4_utcb_t *utcb = l4_utcb()) noexcept
00068     { return trigger(utcb); }
00069
00089     l4_msgtag_t down(l4_timeout_t timeout = L4_IPC_NEVER,
00090                     l4_utcb_t *utcb = l4_utcb()) noexcept
00091     { return l4_semaphore_down_u(cap(), timeout, utcb); }
00092 };
00093
00094 }
```

## 16.569 l4/sys/semaphore.h File Reference


C semaphore interface.

```
#include <l4/sys/irq.h>
```

Include dependency graph for semaphore.h:



This graph shows which files directly or indirectly include this file:



## Functions

- [l4\\_msgtag\\_t l4\\_semaphore\\_up\(l4\\_cap\\_idx\\_t sem\) L4\\_NOTHROW](#)



*Semaphore up operation (wrapper for trigger()).*

- `l4_msgtag_t l4_semaphore_down (l4_cap_idx_t sem, l4_timeout_t timeout) L4_NOTHROW`

*Semaphore down operation.*

## 16.569.1 Detailed Description

C semaphore interface.

Definition in file [semaphore.h](#).

## 16.570 semaphore.h

[Go to the documentation of this file.](#)

```

00001
00006 /*
00007  * (c) 2015 Alexander Warg <alexander.warg@kernkonzept.com>
00008  *
00009  * License: see LICENSE.spdx (in this directory or the directories above)
00010  */
00011
00012 #pragma once
00013
00014 #include <l4/sys/irq.h>
00015
00024
00025 enum l4_semaphore_op
00026 {
00027     L4_SEMAPHORE_OP_DOWN = 0,
00028     // semaphore up is IRQ_OP_TRIGGER with IRQ/Triggerable protocol
00029 };
00030
00044 L4_INLINE l4_msgtag_t
00045 l4_semaphore_up(l4_cap_idx_t sem) L4_NOTHROW
00046 {
00047     return l4_irq_trigger(sem);
00048 }
00049
00053 L4_INLINE l4_msgtag_t
00054 l4_semaphore_up_u(l4_cap_idx_t sem, l4_utcb_t *utcb) L4_NOTHROW
00055 {
00056     return l4_irq_trigger_u(sem, utcb);
00057 }
00058
00078 L4_INLINE l4_msgtag_t
00079 l4_semaphore_down(l4_cap_idx_t sem, l4_timeout_t timeout) L4_NOTHROW;
00080
00084 L4_INLINE l4_msgtag_t
00085 l4_semaphore_down_u(l4_cap_idx_t sem, l4_timeout_t to,
00086                    l4_utcb_t *utcb) L4_NOTHROW;
00087
00088
00089 L4_INLINE l4_msgtag_t
00090 l4_semaphore_down_u(l4_cap_idx_t sem, l4_timeout_t to,
00091                    l4_utcb_t *utcb) L4_NOTHROW
00092 {
00093     l4_msg_regs_t *m = l4_utcb_mr_u(utcb);
00094     m->mr[0] = L4_SEMAPHORE_OP_DOWN;
00095     return l4_ipc_call(sem, utcb, l4_msgtag(L4_PROTO_SEMAPHORE, 1, 0, 0), to);
00096 }
00097
00098
00099 L4_INLINE l4_msgtag_t
00100 l4_semaphore_down(l4_cap_idx_t sem, l4_timeout_t to) L4_NOTHROW
00101 {
00102     return l4_semaphore_down_u(sem, to, l4_utcb());
00103 }
00104

```



## Namespaces

- namespace [L4](#)  
*L4 low-level kernel interface.*

## Functions

- `template<typename T, typename F, typename SMART>`  
`Smart_cap< T, SMART > L4::cap_cast (Smart_cap< F, SMART > const &c) noexcept`  
*static\_cast for (smart) capabilities.*
- `template<typename T, typename F, typename SMART>`  
`Smart_cap< T, SMART > L4::cap_reinterpret_cast (Smart_cap< F, SMART > const &c) noexcept`  
*reinterpret\_cast for (smart) capabilities.*

### 16.571.1 Detailed Description

L4::Capability class.

#### Author

Alexander Warg [alexander.warg@os.inf.tu-dresden.de](mailto:alexander.warg@os.inf.tu-dresden.de)

Definition in file [smart\\_capability](#).

## 16.572 smart\_capability

[Go to the documentation of this file.](#)

```
00001 // vim:set ft=cpp: -*- Mode: C++ -*-
00009 /*
00010  * (c) 2008-2009 Author(s)
00011  *      economic rights: Technische Universität Dresden (Germany)
00012  *
00013  * License: see LICENSE.spdx (in this directory or the directories above)
00014  */
00015 #pragma once
00016
00017 #include <l4/sys/capability>
00018
00019 namespace L4 {
00020
00021 template< typename T, typename SMART >
00022 class Smart_cap : public Cap_base, private SMART
00023 {
00024 public:
00025     SMART const &smart() const noexcept { return *this; }
00026
00027     void _delete() noexcept
00028     {
00029         SMART::free(const_cast<Smart_cap<T, SMART>&>(*this));
00030     }
00031
00032     Cap<T> release() const noexcept
00033     {
00034         l4_cap_idx_t r = cap();
00035         SMART::invalidate(const_cast<Smart_cap<T, SMART>&>(*this));
00036
00037         return Cap<T>(r);
00038     }
00039
00040     void reset() noexcept
00041     {
00042         _c = L4_INVALID_CAP;
00043     }
00044 }
```

```

00047     }
00048
00049     Smart_cap() noexcept : Cap_base(Invalid) {}
00050
00051     Smart_cap(Cap_base::Cap_type t) noexcept : Cap_base(t) {}
00052
00061     template< typename O >
00062     Smart_cap(Cap<O> const &p) noexcept : Cap_base(p.cap())
00063     { Cap<T>::template check_convertible_from<O>(); }
00064
00065     template< typename O >
00066     Smart_cap(Cap<O> const &p, SMART const &smart) noexcept
00067     : Cap_base(p.cap()), SMART(smart)
00068     { Cap<T>::template check_convertible_from<O>(); }
00069
00070     template< typename O >
00071     Smart_cap(Smart_cap<O, SMART> const &o) noexcept
00072     : Cap_base(SMART::copy(o)), SMART(o.smart())
00073     { Cap<T>::template check_convertible_from<O>(); }
00074
00075     Smart_cap(Smart_cap const &o) noexcept
00076     : Cap_base(SMART::copy(o)), SMART(o.smart())
00077     { }
00078
00079     template< typename O >
00080     Smart_cap(typename Cap<O>::Cap_type cap) noexcept : Cap_base(cap)
00081     { Cap<T>::template check_convertible_from<O>(); }
00082
00083     void operator = (typename Cap<T>::Cap_type cap) noexcept
00084     {
00085         _delete();
00086         _c = cap;
00087     }
00088
00089     template< typename O >
00090     void operator = (Smart_cap<O, SMART> const &o) noexcept
00091     {
00092         _delete();
00093         _c = this->SMART::copy(o).cap();
00094         this->SMART::operator = (o.smart());
00095         // return *this;
00096     }
00097
00098     Smart_cap const &operator = (Smart_cap const &o) noexcept
00099     {
00100         if (&o == this)
00101             return *this;
00102
00103         _delete();
00104         _c = this->SMART::copy(o).cap();
00105         this->SMART::operator = (o.smart());
00106         return *this;
00107     }
00108
00109 #if __cplusplus >= 201103L
00110     template< typename O >
00111     Smart_cap(Smart_cap<O, SMART> &&o) noexcept
00112     : Cap_base(o.release()), SMART(o.smart())
00113     { Cap<T>::template check_convertible_from<O>(); }
00114
00115     Smart_cap(Smart_cap &&o) noexcept
00116     : Cap_base(o.release()), SMART(o.smart())
00117     { }
00118
00119     template< typename O >
00120     void operator = (Smart_cap<O, SMART> &&o) noexcept
00121     {
00122         _delete();
00123         _c = o.release().cap();
00124         this->SMART::operator = (o.smart());
00125         // return *this;
00126     }
00127
00128     Smart_cap const &operator = (Smart_cap &&o) noexcept
00129     {
00130         if (&o == this)
00131             return *this;
00132
00133         _delete();
00134         _c = o.release().cap();
00135         this->SMART::operator = (o.smart());
00136         return *this;
00137     }
00138 #endif
00139
00143     Cap<T> operator -> () const noexcept { return Cap<T>(_c); }
00144

```

```

00145     Cap<T> get() const noexcept { return Cap<T>(_c); }
00146
00147     ~Smart_cap() noexcept { _delete(); }
00148 };
00149
00150 template< typename T >
00151 class Weak_cap : public Cap_base
00152 {
00153 public:
00154     Weak_cap() noexcept : Cap_base(Invalid) {}
00155
00156     template< typename O >
00157     Weak_cap(typename Cap<O>::Cap_type t) noexcept : Cap_base(t)
00158     { Cap<T>::template check_convertible_from<O>(); }
00159
00160     template< typename O, typename S >
00161     Weak_cap(Smart_cap<O, S> const &c) noexcept : Cap_base(c.cap())
00162     { Cap<T>::template check_convertible_from<O>(); }
00163
00164     Weak_cap(Weak_cap const &o) noexcept : Cap_base(o) {}
00165
00166     template< typename O >
00167     Weak_cap(Weak_cap<O> const &o) noexcept : Cap_base(o)
00168     { Cap<T>::template check_convertible_from<O>(); }
00169 };
00170
00171 namespace Cap_traits {
00172     template< typename T1, typename T2 >
00173     struct Type { enum { Equal = false }; };
00174
00175     template< typename T1 >
00176     struct Type<T1, T1> { enum { Equal = true }; };
00177 };
00178
00179 template< typename T, typename F, typename SMART >
00180 inline
00181 Smart_cap<T, SMART> cap_cast(Smart_cap<F, SMART> const &c) noexcept
00182 {
00183     Cap<T>::template check_castable_from<F>();
00184     return Smart_cap<T, SMART>(Cap<T>(SMART::copy(c).cap()));
00185 }
00186
00187 template< typename T, typename F, typename SMART >
00188 inline
00189 Smart_cap<T, SMART> cap_reinterpret_cast(Smart_cap<F, SMART> const &c) noexcept
00190 {
00191     return Smart_cap<T, SMART>(Cap<T>(SMART::copy(c).cap()));
00192 }
00193
00194 template< typename T, typename F, typename SMART >
00195 inline
00196 Smart_cap<T, SMART> cap_reinterpret_cast(Smart_cap<F, SMART> const &c) noexcept
00197 {
00198     return Smart_cap<T, SMART>(Cap<T>(SMART::copy(c).cap()));
00199 }
00200
00201 template< typename T, typename F, typename SMART >
00202 inline
00203 Smart_cap<T, SMART> cap_reinterpret_cast(Smart_cap<F, SMART> const &c) noexcept
00204 {
00205     return Smart_cap<T, SMART>(Cap<T>(SMART::copy(c).cap()));
00206 }
00207 }

```

## 16.573 l4/sys/snd\_destination File Reference


The C++ Sender destination interface.

```


#include <l4/sys/snd_destination.h>
#include <l4/sys/types.h>
#include <l4/sys/capability>
#include <l4/sys/cxx/ipc_iface>

```

Include dependency graph for `snd_destination`:



This graph shows which files directly or indirectly include this file:



## Namespaces

- namespace [L4](#)  
*L4 low-level kernel interface.*

### 16.573.1 Detailed Description

The C++ Sender destination interface.

Definition in file [snd\\_destination](#).

## 16.574 snd\_destination

[Go to the documentation of this file.](#)

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00002 /*
00003  * (c) 2025 Frank Mehnert <frank.mehnert@kernkonzept.com>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007 #pragma once
00008
00009 #include <l4/sys/snd_destination.h>
00010 #include <l4/sys/types.h>
00011 #include <l4/sys/capability>
00012 #include <l4/sys/cxx/ipc_iface>
00013
00014 namespace L4 {
00015
00016 class L4_EXPORT Snd_destination :
00017     public Kobject_t<Snd_destination, Kobject, L4_PROTO_KOBJECT>
00018 {
00019 };
00020
00021 }

```

## 16.575 l4/sys/snd\_destination.h File Reference


Sender destination endpoint C interface.

```


#include <l4/sys/utcb.h>
#include <l4/sys/types.h>

```

Include dependency graph for snd\_destination.h:



This graph shows which files directly or indirectly include this file:



### 16.575.1 Detailed Description

Sender destination endpoint C interface.

Definition in file [snd\\_destination.h](#).

## 16.576 snd\_destination.h

[Go to the documentation of this file.](#)

```

00001
00005 /*
00006  * (c) 2025 Frank Mehnert <frank.mehnert@kernkonzept.com>
00007  *
00008  * License: see LICENSE.spdx (in this directory or the directories above)
00009  */
00010 #pragma once
00011
00012 #include <l4/sys/utcb.h>
00013 #include <l4/sys/types.h>

```

## 16.577 l4/sys/task File Reference

Common task related definitions.


```

#include <l4/sys/task.h>
#include <l4/sys/capability>


```



Include dependency graph for task:



This graph shows which files directly or indirectly include this file:



## Data Structures

- class [L4::Task](#)

C++ interface of the [Task](#) kernel object, see [Task](#) for the C interface.

## Namespaces

- namespace [L4](#)

[L4](#) low-level kernel interface.

## 16.577.1 Detailed Description

Common task related definitions.

Definition in file [task](#).

## 16.578 task

[Go to the documentation of this file.](#)

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00006 /*
00007  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00008  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00009  *      economic rights: Technische Universität Dresden (Germany)
00010  *
00011  * License: see LICENSE.spdx (in this directory or the directories above)
00012  */
00013
00014 #pragma once
00015
00016 #include <l4/sys/task.h>
00017 #include <l4/sys/capability>
00018
00019 namespace L4 {
00020
00033 class Task :
00034     public Kobject_t<Task, Kobject, L4_PROTO_TASK,
00035         Type_info::Demand_t<2> >
00036 {
00037 public:
00085     l4_msgtag_t map(Cap<Task> const &src_task,
00086                   l4_fpage_t const &snd_fpage, l4_umword_t snd_base,
00087                   l4_utcb_t *utcb = l4_utcb()) noexcept
00088     { return l4_task_map_u(cap(), src_task.cap(), snd_fpage, snd_base, utcb); }
00089
00135     l4_msgtag_t unmap(l4_fpage_t const &fpage,
00136                     l4_umword_t map_mask,
00137                     l4_utcb_t *utcb = l4_utcb()) noexcept
00138     { return l4_task_unmap_u(cap(), fpage, map_mask, utcb); }
00139
00154     l4_msgtag_t unmap_batch(l4_fpage_t const *fpages,
00155                           unsigned num_fpages,
00156                           l4_umword_t map_mask,
00157                           l4_utcb_t *utcb = l4_utcb()) noexcept
00158     { return l4_task_unmap_batch_u(cap(), fpages, num_fpages, map_mask, utcb); }
00159
00180     l4_msgtag_t delete_obj(L4::Cap<void> obj,
00181                          l4_utcb_t *utcb = l4_utcb()) noexcept
00182     { return l4_task_delete_obj_u(cap(), obj.cap(), utcb); }
00183
00201     l4_msgtag_t release_cap(L4::Cap<void> cap,
00202                          l4_utcb_t *utcb = l4_utcb()) noexcept
00203     { return l4_task_release_cap_u(this->cap(), cap.cap(), utcb); }
00204
00222     l4_msgtag_t cap_valid(Cap<void> const &cap,
00223                          l4_utcb_t *utcb = l4_utcb()) noexcept
00224     { return l4_task_cap_valid_u(this->cap(), cap.cap(), utcb); }
00225
00251     l4_msgtag_t cap_equal(Cap<void> const &cap_a,
00252                          Cap<void> const &cap_b,
00253                          l4_utcb_t *utcb = l4_utcb()) noexcept
00254     { return l4_task_cap_equal_u(cap(), cap_a.cap(), cap_b.cap(), utcb); }
00255
00281     l4_msgtag_t add_ku_mem(l4_fpage_t *fpage,
00282                          l4_utcb_t *utcb = l4_utcb()) noexcept
00283     { return l4_task_add_ku_mem_u(cap(), fpage, utcb); }
00284
00285 };
00286 }
00287
00288

```

## 16.579 task.h

```
00001 /*
00002  * Copyright (C) 2026 Kernkonzept GmbH.
00003  * Author(s): Jan Klötzke <jan.kloetzke@kernkonzept.com>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007 #pragma once
```

## 16.580 task.h

```
00001 /*
00002  * (c) 2018 Adam Lackorzynski <adam@l4re.org>
00003  *
00004  * License: see LICENSE.spdx (in this directory or the directories above)
00005  */
00006 #pragma once
00007
00008 #include <l4/sys/__task-arm.h>
```

## 16.581 task.h


```
00001 /*
00002  * (c) 2018 Adam Lackorzynski <adam@l4re.org>
00003  *
00004  * License: see LICENSE.spdx (in this directory or the directories above)
00005  */
00006 #pragma once
00007
00008 #include <l4/sys/__task-arm.h>
```

## 16.582 I4/sys/task.h File Reference


### Common task related definitions.

```
#include <linux/types.h>
#include <linux/utcb.h>
#include <linux/ipc.h>
#include <linux/arch/task.h>
```

Include dependency graph for task.h:



This graph shows which files directly or indirectly include this file:



## Enumerations

- enum `L4_task_ops` {  
`L4_TASK_MAP_OP` = 0UL , `L4_TASK_UNMAP_OP` = 1UL , `L4_TASK_CAP_INFO_OP` = 2UL ,  
`L4_TASK_ADD_KU_MEM_OP` = 3UL ,  
`L4_TASK_LDT_SET_X86_OP` = 0x11UL , `L4_TASK_MAP_VGICC_ARM_OP` = 0x12UL }

*Operations on task objects.*

## Functions

- `l4_msgtag_t l4_task_map` (`l4_cap_idx_t` dst\_task, `l4_cap_idx_t` src\_task, `l4_fpage_t` snd\_fpage, `l4_umword_t` snd\_base) `L4_NOTHROW`  
*Map resources available in the source task to a destination task.*
- `l4_msgtag_t l4_task_unmap` (`l4_cap_idx_t` task, `l4_fpage_t` fpage, `l4_umword_t` map\_mask) `L4_NOTHROW`  
*Revoke rights from the task.*
- `l4_msgtag_t l4_task_unmap_batch` (`l4_cap_idx_t` task, `l4_fpage_t` const \*fpages, unsigned num\_fpages, `l4_umword_t` map\_mask) `L4_NOTHROW`  
*Revoke rights from a task.*
- `l4_msgtag_t l4_task_delete_obj` (`l4_cap_idx_t` task, `l4_cap_idx_t` obj) `L4_NOTHROW`  
*Release capability and delete object.*
- `l4_msgtag_t l4_task_release_cap` (`l4_cap_idx_t` task, `l4_cap_idx_t` cap) `L4_NOTHROW`  
*Release object capability.*
- `l4_msgtag_t l4_task_cap_valid` (`l4_cap_idx_t` task, `l4_cap_idx_t` cap) `L4_NOTHROW`  
*Check whether a capability is present (refers to an object).*
- `l4_msgtag_t l4_task_cap_equal` (`l4_cap_idx_t` task, `l4_cap_idx_t` cap\_a, `l4_cap_idx_t` cap\_b) `L4_NOTHROW`  
*Test whether two capabilities point to the same object with the same permissions (only considering selected permissions).*
- `l4_msgtag_t l4_task_add_ku_mem` (`l4_cap_idx_t` task, `l4_fpage_t` \*ku\_mem) `L4_NOTHROW`  
*Add kernel-user memory.*

### 16.582.1 Detailed Description

Common task related definitions.

Definition in file [task.h](#).

## 16.583 task.h

[Go to the documentation of this file.](#)

```

00001
00005 /*
00006  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00007  *      Alexander Warg <warg@os.inf.tu-dresden.de>,
00008  *      Björn Döbel <doebel@os.inf.tu-dresden.de>,
00009  *      Torsten Frenzel <frenzel@os.inf.tu-dresden.de>
00010  *      economic rights: Technische Universität Dresden (Germany)
00011  *
00012  * License: see LICENSE.spdx (in this directory or the directories above)
00013  */
00014 #pragma once
00015 #include <l4/sys/types.h>
00016 #include <l4/sys/utcb.h>
00017
00031
00079 L4_INLINE l4_msgtag_t
00080 l4_task_map(l4_cap_idx_t dst_task, l4_cap_idx_t src_task,
00081            l4_fpage_t snd_fpage, l4_umword_t snd_base) L4_NOTHROW;
00082
00086 L4_INLINE l4_msgtag_t
00087 l4_task_map_u(l4_cap_idx_t dst_task, l4_cap_idx_t src_task,
00088              l4_fpage_t snd_fpage, l4_umword_t snd_base, l4_utcb_t *utcb) L4_NOTHROW;
00089
00134 L4_INLINE l4_msgtag_t
00135 l4_task_unmap(l4_cap_idx_t task, l4_fpage_t fpage,
00136              l4_umword_t map_mask) L4_NOTHROW;
00137
00141 L4_INLINE l4_msgtag_t
00142 l4_task_unmap_u(l4_cap_idx_t task, l4_fpage_t fpage,
00143                 l4_umword_t map_mask, l4_utcb_t *utcb) L4_NOTHROW;
00144
00164 L4_INLINE l4_msgtag_t
00165 l4_task_unmap_batch(l4_cap_idx_t task, l4_fpage_t const *fpages,
00166                     unsigned num_fpages, l4_umword_t map_mask) L4_NOTHROW;
00167
00171 L4_INLINE l4_msgtag_t
00172 l4_task_unmap_batch_u(l4_cap_idx_t task, l4_fpage_t const *fpages,
00173                       unsigned num_fpages, l4_umword_t map_mask,
00174                       l4_utcb_t *u) L4_NOTHROW;
00175
00197 L4_INLINE l4_msgtag_t
00198 l4_task_delete_obj(l4_cap_idx_t task, l4_cap_idx_t obj) L4_NOTHROW;
00199
00203 L4_INLINE l4_msgtag_t
00204 l4_task_delete_obj_u(l4_cap_idx_t task, l4_cap_idx_t obj,
00205                      l4_utcb_t *u) L4_NOTHROW;
00206
00225 L4_INLINE l4_msgtag_t
00226 l4_task_release_cap(l4_cap_idx_t task, l4_cap_idx_t cap) L4_NOTHROW;
00227
00231 L4_INLINE l4_msgtag_t
00232 l4_task_release_cap_u(l4_cap_idx_t task, l4_cap_idx_t cap,
00233                       l4_utcb_t *u) L4_NOTHROW;
00234
00235
00253 L4_INLINE l4_msgtag_t
00254 l4_task_cap_valid(l4_cap_idx_t task, l4_cap_idx_t cap) L4_NOTHROW;
00255
00259 L4_INLINE l4_msgtag_t
00260 l4_task_cap_valid_u(l4_cap_idx_t task, l4_cap_idx_t cap, l4_utcb_t *utcb) L4_NOTHROW;
00261
00289 L4_INLINE l4_msgtag_t
00290 l4_task_cap_equal(l4_cap_idx_t task, l4_cap_idx_t cap_a,
00291                  l4_cap_idx_t cap_b) L4_NOTHROW;
00292
00296 L4_INLINE l4_msgtag_t
00297 l4_task_add_ku_mem_u(l4_cap_idx_t task, l4_fpage_t *ku_mem,
00298                     l4_utcb_t *u) L4_NOTHROW;
00299
00326 L4_INLINE l4_msgtag_t
00327 l4_task_add_ku_mem(l4_cap_idx_t task, l4_fpage_t *ku_mem) L4_NOTHROW;
00328
00329
00333 L4_INLINE l4_msgtag_t
00334 l4_task_cap_equal_u(l4_cap_idx_t task, l4_cap_idx_t cap_a,
00335                     l4_cap_idx_t cap_b, l4_utcb_t *utcb) L4_NOTHROW;
00336
00341 enum L4_task_ops
00342 {
00343     L4_TASK_MAP_OP          = 0UL,
00344     L4_TASK_UNMAP_OP       = 1UL,
00345     L4_TASK_CAP_INFO_OP    = 2UL,

```

```

00346     L4_TASK_ADD_KU_MEM_OP      = 3UL,
00347     L4_TASK_LDT_SET_X86_OP      = 0x11UL,
00348     L4_TASK_MAP_VGICC_ARM_OP    = 0x12UL,
00349 };
00350
00351
00352 /* IMPLEMENTATION ----- */
00353
00354 #include <l4/sys/ipc.h>
00355
00356
00357 L4_INLINE l4_msgtag_t
00358 l4_task_map_u(l4_cap_idx_t dst_task, l4_cap_idx_t src_task,
00359              l4_fpage_t snd_fpage, l4_umword_t snd_base, l4_utcb_t *u) L4_NOTHROW
00360 {
00361     l4_msg_regs_t *v = l4_utcb_mr_u(u);
00362     v->mr[0] = L4_TASK_MAP_OP;
00363     v->mr[3] = l4_map_obj_control(0,0);
00364     v->mr[4] = l4_obj_fpage(src_task, 0, L4_CAP_FPAGE_RWS).raw;
00365     v->mr[1] = snd_base;
00366     v->mr[2] = snd_fpage.raw;
00367     return l4_ipc_call(dst_task, u, l4_msgtag(L4_PROTO_TASK, 3, 1, 0), L4_IPC_NEVER);
00368 }
00369
00370 L4_INLINE l4_msgtag_t
00371 l4_task_unmap_u(l4_cap_idx_t task, l4_fpage_t fpage,
00372                l4_umword_t map_mask, l4_utcb_t *u) L4_NOTHROW
00373 {
00374     l4_msg_regs_t *v = l4_utcb_mr_u(u);
00375     v->mr[0] = L4_TASK_UNMAP_OP;
00376     v->mr[1] = map_mask;
00377     v->mr[2] = fpage.raw;
00378     return l4_ipc_call(task, u, l4_msgtag(L4_PROTO_TASK, 3, 0, 0), L4_IPC_NEVER);
00379 }
00380
00381 L4_INLINE l4_msgtag_t
00382 l4_task_unmap_batch_u(l4_cap_idx_t task, l4_fpage_t const *fpages,
00383                      unsigned num_fpages, l4_umword_t map_mask,
00384                      l4_utcb_t *u) L4_NOTHROW
00385 {
00386     l4_msg_regs_t *v = l4_utcb_mr_u(u);
00387     v->mr[0] = L4_TASK_UNMAP_OP;
00388     v->mr[1] = map_mask;
00389     __builtin_memcpy(&v->mr[2], fpages, num_fpages * sizeof(l4_fpage_t));
00390     return l4_ipc_call(task, u, l4_msgtag(L4_PROTO_TASK, 2 + num_fpages, 0, 0), L4_IPC_NEVER);
00391 }
00392
00393 L4_INLINE l4_msgtag_t
00394 l4_task_cap_valid_u(l4_cap_idx_t task, l4_cap_idx_t cap, l4_utcb_t *u) L4_NOTHROW
00395 {
00396     l4_msg_regs_t *v = l4_utcb_mr_u(u);
00397     v->mr[0] = L4_TASK_CAP_INFO_OP;
00398     v->mr[1] = cap & ~1UL;
00399     return l4_ipc_call(task, u, l4_msgtag(L4_PROTO_TASK, 2, 0, 0), L4_IPC_NEVER);
00400 }
00401
00402 L4_INLINE l4_msgtag_t
00403 l4_task_cap_equal_u(l4_cap_idx_t task, l4_cap_idx_t cap_a,
00404                    l4_cap_idx_t cap_b, l4_utcb_t *u) L4_NOTHROW
00405 {
00406     l4_msg_regs_t *v = l4_utcb_mr_u(u);
00407     v->mr[0] = L4_TASK_CAP_INFO_OP;
00408     v->mr[1] = cap_a;
00409     v->mr[2] = cap_b;
00410     return l4_ipc_call(task, u, l4_msgtag(L4_PROTO_TASK, 3, 0, 0), L4_IPC_NEVER);
00411 }
00412
00413 L4_INLINE l4_msgtag_t
00414 l4_task_add_ku_mem_u(l4_cap_idx_t task, l4_fpage_t *ku_mem,
00415                     l4_utcb_t *u) L4_NOTHROW
00416 {
00417     l4_msg_regs_t *v = l4_utcb_mr_u(u);
00418     l4_msgtag_t ret;
00419     v->mr[0] = L4_TASK_ADD_KU_MEM_OP;
00420     v->mr[1] = ku_mem->raw;
00421     ret = l4_ipc_call(task, u, l4_msgtag(L4_PROTO_TASK, 2, 0, 0), L4_IPC_NEVER);
00422     if (!l4_msgtag_has_error(ret))
00423     {
00424         l4_msg_regs_t *v = l4_utcb_mr_u(u);
00425         ku_mem->raw = v->mr[0];
00426     }
00427     return ret;
00428 }
00429
00430
00431
00432 L4_INLINE l4_msgtag_t

```

```

00433 l4_task_map(l4_cap_idx_t dst_task, l4_cap_idx_t src_task,
00434             l4_fpage_t snd_fpage, l4_umword_t snd_base) L4_NOTHROW
00435 {
00436     return l4_task_map_u(dst_task, src_task, snd_fpage, snd_base, l4_utcb());
00437 }
00438
00439 L4_INLINE l4_msgtag_t
00440 l4_task_unmap(l4_cap_idx_t task, l4_fpage_t fpage,
00441             l4_umword_t map_mask) L4_NOTHROW
00442 {
00443     return l4_task_unmap_u(task, fpage, map_mask, l4_utcb());
00444 }
00445
00446 L4_INLINE l4_msgtag_t
00447 l4_task_unmap_batch(l4_cap_idx_t task, l4_fpage_t const *fpages,
00448                   unsigned num_fpages, l4_umword_t map_mask) L4_NOTHROW
00449 {
00450     return l4_task_unmap_batch_u(task, fpages, num_fpages, map_mask,
00451                                 l4_utcb());
00452 }
00453
00454 L4_INLINE l4_msgtag_t
00455 l4_task_delete_obj_u(l4_cap_idx_t task, l4_cap_idx_t obj,
00456                   l4_utcb_t *u) L4_NOTHROW
00457 {
00458     return l4_task_unmap_u(task, l4_obj_fpage(obj, 0, L4_CAP_FPAGE_RWSD),
00459                           L4_FP_DELETE_OBJ, u);
00460 }
00461
00462 L4_INLINE l4_msgtag_t
00463 l4_task_delete_obj(l4_cap_idx_t task, l4_cap_idx_t obj) L4_NOTHROW
00464 {
00465     return l4_task_delete_obj_u(task, obj, l4_utcb());
00466 }
00467
00468 L4_INLINE l4_msgtag_t
00469 l4_task_release_cap_u(l4_cap_idx_t task, l4_cap_idx_t cap,
00470                   l4_utcb_t *u) L4_NOTHROW
00471 {
00472     return l4_task_unmap_u(task, l4_obj_fpage(cap, 0, L4_CAP_FPAGE_RWSD),
00473                           L4_FP_ALL_SPACES, u);
00474 }
00475
00476 L4_INLINE l4_msgtag_t
00477 l4_task_release_cap(l4_cap_idx_t task, l4_cap_idx_t cap) L4_NOTHROW
00478 {
00479     return l4_task_release_cap_u(task, cap, l4_utcb());
00480 }
00481
00482 L4_INLINE l4_msgtag_t
00483 l4_task_cap_valid(l4_cap_idx_t task, l4_cap_idx_t cap) L4_NOTHROW
00484 {
00485     return l4_task_cap_valid_u(task, cap, l4_utcb());
00486 }
00487
00488 L4_INLINE l4_msgtag_t
00489 l4_task_cap_equal(l4_cap_idx_t task, l4_cap_idx_t cap_a,
00490                 l4_cap_idx_t cap_b) L4_NOTHROW
00491 {
00492     return l4_task_cap_equal_u(task, cap_a, cap_b, l4_utcb());
00493 }
00494
00495 L4_INLINE l4_msgtag_t
00496 l4_task_add_ku_mem(l4_cap_idx_t task, l4_fpage_t *ku_mem) L4_NOTHROW
00497 {
00498     return l4_task_add_ku_mem_u(task, ku_mem, l4_utcb());
00499 }
00500
00501
00502 #include <l4/sys/arch/task.h>

```

## 16.584 task.h


```

00001 /*
00002  * Copyright (C) 2026 Kernkonzept GmbH.
00003  * Author(s): Jan Klötzke <jan.kloetzke@kernkonzept.com>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007 #pragma once


```

### Thread implementation.

```
#include <linux/sys/capability>
#include <linux/types.h>
Include dependency graph for thread:
```



This graph shows which files directly or indirectly include this file:



## Namespaces

- namespace **cxx**  
*Our C++ library.*



## 16.585.1 Detailed Description

Thread implementation.

Definition in file [thread](#).

## 16.586 thread

[Go to the documentation of this file.](#)

```

00001 // vim:set ft=cpp: -*- Mode: C++ -*-
00002 /*
00003  * (c) 2004-2009 Alexander Warg <warg@os.inf.tu-dresden.de>
00004  *     economic rights: Technische Universität Dresden (Germany)
00005  * This file is part of TUD:OS and distributed under the terms of the
00006  * GNU Lesser General Public License 2.1.
00007  * Please see the COPYING-LGPL-2.1 file for details.
00008 */
00009
00010 #ifndef CXX_THREAD_H__
00011 #define CXX_THREAD_H__
00012
00013 #include <l4/sys/capability>
00014 #include <l4/sys/types.h>
00015
00016 namespace cxx {
00017
00018     class Thread
00019     {
00020     public:
00021
00022         enum State
00023         {
00024             Dead      = 0,
00025             Running   = 1,
00026             Stopped   = 2,
00027         };
00028
00029         Thread(bool initiate);
00030         Thread(void *stack);
00031         Thread(void *stack, L4::Cap<L4::Thread> const &cap);
00032         virtual ~Thread();
00033         void execute() asm ("L4_Thread_execute");
00034         virtual void run() = 0;
00035         virtual void shutdown() asm ("L4_Thread_shutdown");
00036         void start();
00037         void stop();
00038
00039         L4::Cap<L4::Thread> self() const throw()
00040         { return _cap; }
00041
00042         State state() const
00043         { return _state; }
00044
00045         static void start_cxx_thread(Thread *_this)
00046             asm ("L4_Thread_start_cxx_thread");
00047
00048         static void kill_cxx_thread(Thread *_this)
00049             asm ("L4_Thread_kill_cxx_thread");
00050
00051         static void set_pager(L4::Cap<void>const &p) throw()
00052         { _pager = p; }
00053
00054     private:
00055         int create();
00056
00057         L4::Cap<L4::Thread> _cap;
00058         State _state;
00059
00060     protected:
00061         void *_stack;
00062
00063     private:
00064         static L4::Cap<void> _pager;
00065         static L4::Cap<void> _master;
00066     };
00067
00068 };
00069
00070 #endif /* CXX_THREAD_H__ */
00071

```



## Namespaces

- namespace [L4](#)  
*L4 low-level kernel interface.*

### 16.587.1 Detailed Description

Common thread related definitions.

Definition in file [thread](#).

## 16.588 thread

[Go to the documentation of this file.](#)

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00006 /*
00007  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00008  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00009  *      economic rights: Technische Universität Dresden (Germany)
00010  *
00011  * License: see LICENSE.spdx (in this directory or the directories above)
00012  */
00013
00014 #pragma once
00015
00016 #include <l4/sys/capability>
00017 #include <l4/sys/snd_destination>
00018 #include <l4/sys/thread.h>
00019
00020 namespace L4 {
00021
00022 class Thread :
00023     public Kobject_t<Thread, Snd_destination, L4_PROTO_THREAD,
00024         Type_info::Demand_t<1> >
00025 {
00026 public:
00027     l4_msgtag_t ex_regs(l4_addr_t ip, l4_addr_t sp,
00028         l4_umword_t flags,
00029         l4_utcb_t *utcb = l4_utcb()) noexcept
00030     { return l4_thread_ex_regs_u(cap(), ip, sp, flags, utcb); }
00031
00032     l4_msgtag_t ex_regs(l4_addr_t *ip, l4_addr_t *sp,
00033         l4_umword_t *flags,
00034         l4_utcb_t *utcb = l4_utcb()) noexcept
00035     { return l4_thread_ex_regs_ret_u(cap(), ip, sp, flags, utcb); }
00036
00037     class Attr
00038     {
00039     private:
00040         friend class L4::Thread;
00041         l4_utcb_t *_u;
00042
00043     public:
00044         explicit Attr(l4_utcb_t *utcb = l4_utcb()) noexcept : _u(utcb)
00045         { l4_thread_control_start_u(utcb); }
00046
00047         void pager(Cap<void> const &pager) noexcept
00048         { l4_thread_control_pager_u(pager.cap(), _u); }
00049
00050         Cap<void> pager() noexcept
00051         { return Cap<void>(l4_utcb_mr_u(_u)->mr[1]); }
00052
00053         void exc_handler(Cap<void> const &exc_handler) noexcept
00054         { l4_thread_control_exc_handler_u(exc_handler.cap(), _u); }
00055
00056         Cap<void> exc_handler() noexcept
00057         { return Cap<void>(l4_utcb_mr_u(_u)->mr[2]); }
00058
00059         void bind(l4_utcb_t *thread_utcb, Cap<Task> const &task) noexcept
00060         { l4_thread_control_bind_u(thread_utcb, task.cap(), _u); }
00061
00062         void alien(int on) noexcept

```

```

00225     { l4_thread_control_alien_u(_u, on); }
00226 };
00227
00243 l4_msgtag_t control(Attr const &attr) noexcept
00244 { return l4_thread_control_commit_u(cap(), attr._u); }
00245
00253 l4_msgtag_t switch_to(l4_utcb_t *utcb = l4_utcb()) noexcept
00254 { return l4_thread_switch_u(cap(), utcb); }
00255
00264 l4_msgtag_t stats_time(l4_kernel_clock_t *us,
00265                        l4_utcb_t *utcb = l4_utcb()) noexcept
00266 { return l4_thread_stats_time_u(cap(), us, utcb); }
00267
00283 l4_msgtag_t vcpu_resume_start(l4_utcb_t *utcb = l4_utcb()) noexcept
00284 { return l4_thread_vcpu_resume_start_u(utcb); }
00285
00334 l4_msgtag_t vcpu_resume_commit(l4_msgtag_t tag,
00335                                l4_utcb_t *utcb = l4_utcb()) noexcept
00336 { return l4_thread_vcpu_resume_commit_u(cap(), tag, utcb); }
00337
00358 l4_msgtag_t vcpu_control(l4_addr_t vcpu_state, l4_utcb_t *utcb = l4_utcb())
00359     noexcept
00360 { return l4_thread_vcpu_control_u(cap(), vcpu_state, utcb); }
00361
00398 l4_msgtag_t vcpu_control_ext(l4_addr_t ext_vcpu_state,
00399                               l4_utcb_t *utcb = l4_utcb()) noexcept
00400 { return l4_thread_vcpu_control_ext_u(cap(), ext_vcpu_state, utcb); }
00401
00427 l4_msgtag_t register_del_irq(Cap<Irq> irq, l4_utcb_t *u = l4_utcb()) noexcept
00428 { return l4_thread_register_del_irq_u(cap(), irq.cap(), u); }
00429
00448 class Modify_senders
00449 {
00450 private:
00451     friend class Thread;
00452     l4_utcb_t *utcb;
00453     unsigned cnt;
00454
00455 public:
00456     explicit Modify_senders(l4_utcb_t *u = l4_utcb()) noexcept
00457         : utcb(u), cnt(1)
00458     {
00459         l4_utcb_mr_u(utcb)->mr[0] = L4_THREAD_MODIFY_SENDER_OP;
00460     }
00461
00481 int add(l4_umword_t match_mask, l4_umword_t match,
00482         l4_umword_t del_bits, l4_umword_t add_bits) noexcept
00483 {
00484     l4_msg_regs_t *m = l4_utcb_mr_u(utcb);
00485     if (cnt >= L4_UTCB_GENERIC_DATA_SIZE - 4)
00486         return -L4_ENOMEM;
00487     m->mr[cnt++] = match_mask;
00488     m->mr[cnt++] = match;
00489     m->mr[cnt++] = del_bits;
00490     m->mr[cnt++] = add_bits;
00491     return 0;
00492 }
00493 };
00494
00525 l4_msgtag_t modify_senders(Modify_senders const &todo) noexcept
00526 {
00527     return l4_ipc_call(cap(), todo.utcb, l4_msgtag(L4_PROTO_THREAD, todo.cnt, 0, 0), L4_IPC_NEVER);
00528 }
00529
00553 l4_msgtag_t register_doorbell_irq(Cap<Irq> irq, l4_utcb_t *u = l4_utcb()) noexcept
00554 { return l4_thread_register_doorbell_irq_u(cap(), irq.cap(), u); }
00555 };
00556 }

```

## 16.589 l4/sys/thread\_group File Reference

```

#include <l4/sys/capability>
#include <l4/sys/thread_group.h>

```



```

00053  l4_msgtag_t add(Cap<Thread> thread, l4_utcb_t *utcb = l4_utcb()) noexcept
00054  { return l4_thread_group_add_u(cap(), thread.cap(), utcb); }
00055
00067  l4_msgtag_t remove(Cap<Thread> thread, l4_utcb_t *utcb = l4_utcb()) noexcept
00068  { return l4_thread_group_remove_u(cap(), thread.cap(), utcb); }
00069  };
00070
00071  }


```

## 16.591 I4/sys/thread\_group.h File Reference


```

#include <l4/sys/types.h>
#include <l4/sys/utcb.h>
#include <l4/sys/ipc.h>
Include dependency graph for thread_group.h:

```



This graph shows which files directly or indirectly include this file:



## Functions

- [l4\\_msgtag\\_t l4\\_thread\\_group\\_add \(l4\\_cap\\_idx\\_t tg, l4\\_cap\\_idx\\_t thread\) L4\\_NOTHROW](#)  
*Add thread to a thread group.*
- [l4\\_msgtag\\_t l4\\_thread\\_group\\_remove \(l4\\_cap\\_idx\\_t tg, l4\\_cap\\_idx\\_t thread\) L4\\_NOTHROW](#)  
*Remove thread from a thread group.*

## 16.592 thread\_group.h

[Go to the documentation of this file.](#)


```

00001 /*
00002  * Copyright (C) 2022-2025 Kernkonzept GmbH.
00003  * Author(s): Adam Lackorzynski <adam@os.inf.tu-dresden.de>
00004  *           Frank Mehnert <frank.mehnert@kernkonzept.com>
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00011 #pragma once
00012
00013 #include <l4/sys/types.h>
00014 #include <l4/sys/utcb.h>
00015
00033
00034 enum l4_thread_group_ops
00035 {
00036     L4_THREAD_GROUP_ADD_OP = 2UL,
00037     L4_THREAD_GROUP_REMOVE_OP = 3UL,
00038 };
00039
00040 enum l4_thread_group_policy
00041 {
00042     L4_THREAD_GROUP_POLICY_STRICT_CORE_LOCAL = 0,
00043     L4_THREAD_GROUP_POLICY_SOFT_CORE_LOCAL = 1,
00044 };
00045
00052 L4_INLINE l4_msgtag_t
00053 l4_thread_group_add(l4_cap_idx_t tg,
00054                    l4_cap_idx_t thread) L4_NOTHROW;
00055
00059 L4_INLINE l4_msgtag_t
00060 l4_thread_group_add_u(l4_cap_idx_t tg,
00061                      l4_cap_idx_t thread,
00062                      l4_utcb_t *utcb) L4_NOTHROW;
00063
00070 L4_INLINE l4_msgtag_t
00071 l4_thread_group_remove(l4_cap_idx_t tg,
00072                       l4_cap_idx_t thread) L4_NOTHROW;
00073
00077 L4_INLINE l4_msgtag_t
00078 l4_thread_group_remove_u(l4_cap_idx_t tg,
00079                          l4_cap_idx_t thread,
00080                          l4_utcb_t *utcb) L4_NOTHROW;
00081
00082
00083 /* IMPLEMENTATION ----- */
00084
00085 #include <l4/sys/ipc.h>
00086
00087 L4_INLINE l4_msgtag_t
00088 l4_thread_group_add_u(l4_cap_idx_t tg,
00089                      l4_cap_idx_t thread,
00090                      l4_utcb_t *utcb) L4_NOTHROW
00091 {
00092     l4_msg_regs_t *v = l4_utcb_mr_u(utcb);
00093     v->mr[0] = L4_THREAD_GROUP_ADD_OP;
00094     v->mr[1] = l4_map_obj_control(0, 0);
00095     v->mr[2] = l4_obj_fpage(thread, 0, L4_CAP_FPAGE_RWS).raw;
00096     return l4_ipc_call(tg, utcb,
00097                       l4_msgtag(L4_PROTO_THREAD_GROUP, 1, 1, 0), L4_IPC_NEVER);
00098 }
00099
00100 L4_INLINE l4_msgtag_t
00101 l4_thread_group_remove_u(l4_cap_idx_t tg,
00102                          l4_cap_idx_t thread,
00103                          l4_utcb_t *utcb) L4_NOTHROW
00104 {
00105     l4_msg_regs_t *v = l4_utcb_mr_u(utcb);

```


## 16.593 I4/sys/typeinfo\_svr File Reference

```
#include <l4/sys/meta>
#include <l4/sys/cxx/ipc_epiface>
Include dependency graph for typeinfo_svr:
```





This graph shows which files directly or indirectly include this file:



## Namespaces

- namespace [L4](#)  
*L4 low-level kernel interface.*

## 16.593.1 Detailed Description

Type information server template.

Definition in file [typeinfo\\_svr](#).

## 16.594 typeinfo\_svr

[Go to the documentation of this file.](#)

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00002 /*
00003  * (c) 2010 Alexander Warg <warg@os.inf.tu-dresden.de>
00004  *      economic rights: Technische Universität Dresden (Germany)
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00008
00009 #pragma once
00010
00011 #include <l4/sys/meta>
00012 #include <l4/sys/cxx/ipc_epiface>
00013
00014 namespace L4 { namespace Util {
00015
00016     template<typename KO, typename IOS>
00017     long handle_meta_request(IOS &ios)
00018     {
00019         using L4::Ipcc::Msg::dispatch_call;
00020         typedef L4::Ipcc::Detail::Meta_svr<KO> Msvr;
00021         typedef L4::Meta::Rpcs Rpc;
00022         Msvr *svr = nullptr;
00023         l4_msgtag_t tag = dispatch_call<Rpc>(svr, ios.utcb(), ios.tag(), 0);
00024         ios.set_ipc_params(tag);
00025         return tag.label();
00026     }
00027 } }
00028
00029 }
```

## 16.595 types.h

```

00001  /*
00002  * (c) 2008-2010 Adam Lackorzynski <adam@os.inf.tu-dresden.de>
00003  *     economic rights: Technische Universität Dresden (Germany)
00004  * License: see LICENSE.spdx (in this directory or the directories above)
00005  */
00006  #pragma once
00007
00008  #include <l4/vbus/vbus_types.h>
00009
00014  enum l4io_iomem_flags_t
00015  {
00016      L4IO_MEM_NONCACHED = 0,
00017      L4IO_MEM_CACHED    = 1,
00018      L4IO_MEM_USE_MTRR   = 2,
00019      L4IO_MEM_ATTR_MASK = 0xf,
00020
00021      // combinations
00022      L4IO_MEM_WRITE_COMBINED = L4IO_MEM_USE_MTRR | L4IO_MEM_CACHED,
00023
00024
00027      L4IO_MEM_USE_RESERVED_AREA = 0x40 « 8,
00029      L4IO_MEM_EAGER_MAP         = 0x80 « 8,
00030  };
00031
00036  enum l4io_device_types_t {
00037      L4IO_DEVICE_INVALID = 0,
00038      L4IO_DEVICE_PCI,
00039      L4IO_DEVICE_USB,
00040      L4IO_DEVICE_OTHER,
00041      L4IO_DEVICE_ANY = ~0
00042  };
00043
00048  enum l4io_resource_types_t {
00049      L4IO_RESOURCE_INVALID = L4VBUS_RESOURCE_INVALID,
00050      L4IO_RESOURCE_IRQ     = L4VBUS_RESOURCE_IRQ,
00051      L4IO_RESOURCE_MEM     = L4VBUS_RESOURCE_MEM,
00052      L4IO_RESOURCE_PORT    = L4VBUS_RESOURCE_PORT,
00053      L4IO_RESOURCE_ANY     = ~0
00054  };
00055
00056
00057  typedef l4vbus_device_handle_t l4io_device_handle_t;
00058  typedef unsigned l4io_resource_handle_t;
00059
00067  typedef l4vbus_resource_t l4io_resource_t;
00068
00072  typedef l4vbus_device_t l4io_device_t;

```

## 16.596 l4/sys/types.h File Reference


Common [L4](#) ABI Data Types.

```


#include <l4/sys/l4int.h>
#include <l4/sys/compiler.h>
#include <l4/sys/consts.h>
#include <l4/sys/__l4_fpage.h>
#include <l4/sys/__timeout.h>

```

Include dependency graph for types.h:



This graph shows which files directly or indirectly include this file:



## Data Structures

- struct [l4\\_msgtag\\_t](#)  
*Message tag data structure.*

## Typedefs

- typedef [l4\\_int16\\_t](#) [l4\\_ret\\_t](#)  
*Return value of an IPC call as well as an RPC call.*
- typedef [l4\\_int16\\_t](#) [l4\\_proto\\_t](#)  
*Prototype value for RPC calls.*
- typedef unsigned long [l4\\_cap\\_idx\\_t](#)  
*Capability selector type.*

## Enumerations

- enum [L4\\_msgtag\\_protocol](#) {  
[L4\\_PROTO\\_NONE](#) = 0 , [L4\\_PROTO\\_ALLOW\\_SYSCALL](#) = 1 , [L4\\_PROTO\\_PF\\_EXCEPTION](#) = 1 ,  
[L4\\_PROTO\\_IRQ](#) = -1L ,  
[L4\\_PROTO\\_PAGE\\_FAULT](#) = -2L , [L4\\_PROTO\\_EXCEPTION](#) = -5L , [L4\\_PROTO\\_SIGMA0](#) = -6L ,  
[L4\\_PROTO\\_IO\\_PAGE\\_FAULT](#) = -8L ,  
[L4\\_PROTO\\_THREAD\\_GROUP](#) = -9L , [L4\\_PROTO\\_KOBJECT](#) = -10L , [L4\\_PROTO\\_TASK](#) = -11L ,  
[L4\\_PROTO\\_THREAD](#) = -12L ,  
[L4\\_PROTO\\_LOG](#) = -13L , [L4\\_PROTO\\_SCHEDULER](#) = -14L , [L4\\_PROTO\\_FACTORY](#) = -15L ,  
[L4\\_PROTO\\_VM](#) = -16L ,  
[L4\\_PROTO\\_DMA\\_SPACE](#) = -17L , [L4\\_PROTO\\_IRQ\\_SENDER](#) = -18L , [L4\\_PROTO\\_SEMAPHORE](#) = -20L ,  
[L4\\_PROTO\\_META](#) = -21L ,  
[L4\\_PROTO\\_IOMMU](#) = -22L , [L4\\_PROTO\\_DEBUGGER](#) = -23L , [L4\\_PROTO\\_SMCCC](#) = -24L ,  
[L4\\_PROTO\\_VCPU\\_CONTEXT](#) = -25L }

*Message tag for IPC operations.*

- enum [L4\\_msgtag\\_flags](#) { [L4\\_MSGTAG\\_ERROR](#) , [L4\\_MSGTAG\\_TRANSFER\\_FPU](#) , [L4\\_MSGTAG\\_SCHEDULE](#) , [L4\\_MSGTAG\\_PROPAGATE](#) = 0x4000 , [L4\\_MSGTAG\\_FLAGS](#) }

*Flags for message tags.*

## Functions

- long [l4\\_msgtag\\_label](#) ([l4\\_msgtag\\_t](#) t) [L4\\_NOTHROW](#)  
*Get the protocol of tag.*
- unsigned [l4\\_msgtag\\_words](#) ([l4\\_msgtag\\_t](#) t) [L4\\_NOTHROW](#)  
*Get the number of untyped words.*
- unsigned [l4\\_msgtag\\_items](#) ([l4\\_msgtag\\_t](#) t) [L4\\_NOTHROW](#)  
*Get the number of typed items.*
- unsigned [l4\\_msgtag\\_flags](#) ([l4\\_msgtag\\_t](#) t) [L4\\_NOTHROW](#)  
*Get the flags.*
- unsigned [l4\\_msgtag\\_has\\_error](#) ([l4\\_msgtag\\_t](#) t) [L4\\_NOTHROW](#)  
*Test for error indicator flag.*
- unsigned [l4\\_msgtag\\_is\\_page\\_fault](#) ([l4\\_msgtag\\_t](#) t) [L4\\_NOTHROW](#)  
*Test for page-fault protocol.*
- unsigned [l4\\_msgtag\\_is\\_exception](#) ([l4\\_msgtag\\_t](#) t) [L4\\_NOTHROW](#)  
*Test for exception protocol.*
- unsigned [l4\\_msgtag\\_is\\_sigma0](#) ([l4\\_msgtag\\_t](#) t) [L4\\_NOTHROW](#)  
*Test for sigma0 protocol.*
- unsigned [l4\\_msgtag\\_is\\_io\\_page\\_fault](#) ([l4\\_msgtag\\_t](#) t) [L4\\_NOTHROW](#)  
*Test for IO-page-fault protocol.*
- [l4\\_msgtag\\_t](#) [l4\\_msgtag](#) (long label, unsigned words, unsigned items, unsigned flags) [L4\\_NOTHROW](#)  
*Create a message tag from the specified values.*
- unsigned [l4\\_is\\_invalid\\_cap](#) ([l4\\_cap\\_idx\\_t](#) c) [L4\\_NOTHROW](#)  
*Test if a capability selector is the invalid capability.*
- unsigned [l4\\_is\\_valid\\_cap](#) ([l4\\_cap\\_idx\\_t](#) c) [L4\\_NOTHROW](#)  
*Test if a capability selector is a valid selector.*
- unsigned [l4\\_capability\\_equal](#) ([l4\\_cap\\_idx\\_t](#) c1, [l4\\_cap\\_idx\\_t](#) c2) [L4\\_NOTHROW](#)  
*Test if the capability indices of two capability selectors are equal.*
- [l4\\_cap\\_idx\\_t](#) [l4\\_capability\\_next](#) ([l4\\_cap\\_idx\\_t](#) c) [L4\\_NOTHROW](#)  
*Get the next capability selector after c.*

## 16.596.1 Detailed Description

Common [L4](#) ABI Data Types.

Definition in file [types.h](#).

## 16.596.2 Typedef Documentation

### 16.596.2.1 l4\_proto\_t

```
typedef l4\_int16\_t l4\_proto\_t
```

Prototype value for RPC calls.

This type must not be larger than the label part of [l4\\_msgtag\\_t](#).

Definition at line 35 of file [types.h](#).

**16.596.2.2 l4\_ret\_t**

```
typedef l4_int16_t l4_ret_t
```

Return value of an IPC call as well as an RPC call.

This type must not be larger than the label part of [l4\\_msgtag\\_t](#).

Definition at line 28 of file [types.h](#).

**16.596.3 Function Documentation****16.596.3.1 l4\_capability\_next()**

```
l4_cap_idx_t l4_capability_next (
    l4_cap_idx_t c) [inline]
```

Get the next capability selector after *c*.

**Parameters**

<i>c</i>	The capability selector for which the next selector shall be computed.
----------	--

**Returns**

The next capability selector after *c*.

Definition at line 473 of file [types.h](#).

References [L4\\_CAP\\_OFFSET](#), [L4\\_INLINE](#), and [L4\\_NOTHROW](#).

**16.597 types.h**

[Go to the documentation of this file.](#)

```
00001 /*****
00002  *
00003  * (c) 2008-2013 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00004  * Alexander Warg <warg@os.inf.tu-dresden.de>,
00005  * Björn Döbel <doebel@os.inf.tu-dresden.de>,
00006  * Torsten Frenzel <frenzel@os.inf.tu-dresden.de>
00007  * economic rights: Technische Universität Dresden (Germany)
00008  *
00009  * License: see LICENSE.spdx (in this directory or the directories above)
00010  */
00011 /*****
00012  *
00013  * #pragma once
00014  *
00015  * #include <l4/sys/l4int.h>
00016  * #include <l4/sys/compiler.h>
00017  * #include <l4/sys/consts.h>
00018  *
00019  * typedef l4_int16_t l4_ret_t;
00020  *
00021  * typedef l4_int16_t l4_proto_t;
00022  *
00023  * enum L4_msgtag_protocol
```

```

00053 {
00054     L4_PROTO_NONE = 0,
00055     L4_PROTO_ALLOW_SYSCALL = 1,
00056     L4_PROTO_PF_EXCEPTION = 1,
00057
00058     L4_PROTO_IRQ = -1L,
00059     L4_PROTO_PAGE_FAULT = -2L,
00060     // -3L unused
00061     // -4L unused
00062     L4_PROTO_EXCEPTION = -5L,
00063     L4_PROTO_SIGMA0 = -6L,
00064     L4_PROTO_IO_PAGE_FAULT = -8L,
00065     L4_PROTO_THREAD_GROUP = -9L,
00066     L4_PROTO_KOBJECT = -10L,
00067     L4_PROTO_TASK = -11L,
00068     L4_PROTO_THREAD = -12L,
00069     L4_PROTO_LOG = -13L,
00070     L4_PROTO_SCHEDULER = -14L,
00071     L4_PROTO_FACTORY = -15L,
00072     L4_PROTO_VM = -16L,
00073     L4_PROTO_DMA_SPACE = -17L,
00074     L4_PROTO_IRQ_SENDER = -18L,
00075     // -19L unused
00076     L4_PROTO_SEMAPHORE = -20L,
00077     L4_PROTO_META = -21L,
00078     L4_PROTO_IOMMU = -22L,
00079     L4_PROTO_DEBUGGER = -23L,
00080     L4_PROTO_SMCCC = -24L,
00081     L4_PROTO_VCPU_CONTEXT = -25L,
00082 };
00083
00084 enum L4_varg_type
00085 {
00086     L4_VARG_TYPE_NIL = 0x00,
00087     L4_VARG_TYPE_UMWORD = 0x01,
00088     L4_VARG_TYPE_MWORD = 0x81,
00089     L4_VARG_TYPE_STRING = 0x02,
00090     L4_VARG_TYPE_FPAGE = 0x03,
00091
00092     L4_VARG_TYPE_SIGN = 0x80,
00093 };
00094
00095
00100 enum L4_msgtag_flags
00101 {
00102     // flags for received IPC
00107     L4_MSGTAG_ERROR = 0x8000,
00108
00109     // flags for sending IPC
00119     L4_MSGTAG_TRANSFER_FPU = 0x1000,
00128     L4_MSGTAG_SCHEDULE = 0x2000,
00141     L4_MSGTAG_PROPAGATE = 0x4000,
00142
00147     L4_MSGTAG_FLAGS = 0xf000,
00148 };
00149
00150 typedef struct l4_msgtag_t l4_msgtag_t;
00151
00160 L4_INLINE long l4_msgtag_label(l4_msgtag_t t) L4_NOTHROW;
00161
00170 L4_INLINE unsigned l4_msgtag_words(l4_msgtag_t t) L4_NOTHROW;
00171
00180 L4_INLINE unsigned l4_msgtag_items(l4_msgtag_t t) L4_NOTHROW;
00181
00192 L4_INLINE unsigned l4_msgtag_flags(l4_msgtag_t t) L4_NOTHROW;
00193
00206 L4_INLINE unsigned l4_msgtag_has_error(l4_msgtag_t t) L4_NOTHROW;
00207
00216 L4_INLINE unsigned l4_msgtag_is_page_fault(l4_msgtag_t t) L4_NOTHROW;
00217
00226 L4_INLINE unsigned l4_msgtag_is_exception(l4_msgtag_t t) L4_NOTHROW;
00227
00236 L4_INLINE unsigned l4_msgtag_is_sigma0(l4_msgtag_t t) L4_NOTHROW;
00237
00246 L4_INLINE unsigned l4_msgtag_is_io_page_fault(l4_msgtag_t t) L4_NOTHROW;
00247
00248
00265 struct l4_msgtag_t
00266 {
00267     l4_mword_t raw;
00268 #ifdef __cplusplus
00270     long label() const L4_NOTHROW { return l4_msgtag_label(*this); }
00272     void label(long v) L4_NOTHROW { raw = (raw & 0xffff) | ((l4_umword_t)v << 16); }
00274     unsigned words() const L4_NOTHROW { return l4_msgtag_words(*this); }
00276     unsigned items() const L4_NOTHROW { return l4_msgtag_items(*this); }
00283     unsigned flags() const L4_NOTHROW { return l4_msgtag_flags(*this); }
00285     bool is_page_fault() const L4_NOTHROW

```

```

00286     { return l4_msgtag_is_page_fault(*this); }
00288     bool is_exception() const L4_NOTHROW
00289     { return l4_msgtag_is_exception(*this); }
00291     bool is_sigma0() const L4_NOTHROW { return l4_msgtag_is_sigma0(*this); }
00293     bool is_io_page_fault() const L4_NOTHROW
00294     { return l4_msgtag_is_io_page_fault(*this); }
00299     bool has_error() const L4_NOTHROW { return l4_msgtag_has_error(*this); }
00300 #endif
00301 };
00302
00303 // The following declaration should be _after_ the definition of struct
00304 // l4_msgtag_t. Circumvents a clang warning about a *potentially*
00305 // incompatibility with C if the type is incomplete when the function is
00306 // declared.
00307
00319 L4_INLINE l4_msgtag_t l4_msgtag(long label, unsigned words, unsigned items,
00320                                unsigned flags) L4_NOTHROW;
00321
00322
00323
00352 typedef unsigned long l4_cap_idx_t;
00353
00363 L4_INLINE unsigned l4_is_invalid_cap(l4_cap_idx_t c) L4_NOTHROW;
00364
00374 L4_INLINE unsigned l4_is_valid_cap(l4_cap_idx_t c) L4_NOTHROW;
00375
00389 L4_INLINE unsigned l4_capability_equal(l4_cap_idx_t c1, l4_cap_idx_t c2) L4_NOTHROW;
00390
00399 L4_INLINE l4_cap_idx_t l4_capability_next(l4_cap_idx_t c) L4_NOTHROW;
00400
00401 /* ***** Implementation ***** */
00402 /* Implementation */
00403
00404 L4_INLINE unsigned
00405 l4_is_invalid_cap(l4_cap_idx_t c) L4_NOTHROW
00406 { return c & L4_INVALID_CAP_BIT; }
00407
00408 L4_INLINE unsigned
00409 l4_is_valid_cap(l4_cap_idx_t c) L4_NOTHROW
00410 { return !(c & L4_INVALID_CAP_BIT); }
00411
00412 L4_INLINE unsigned
00413 l4_capability_equal(l4_cap_idx_t c1, l4_cap_idx_t c2) L4_NOTHROW
00414 { return (c1 >> L4_CAP_SHIFT) == (c2 >> L4_CAP_SHIFT); }
00415
00416
00420 L4_INLINE
00421 l4_msgtag_t l4_msgtag(long label, unsigned words, unsigned items,
00422                      unsigned flags) L4_NOTHROW
00423 {
00424     return (l4_msgtag_t){ (l4_mword_t)((l4_umword_t)label << 16)
00425                          | (l4_mword_t)(words & 0x3f)
00426                          | (l4_mword_t)((items & 0x3f) << 6)
00427                          | (l4_mword_t)(flags & 0xf000)};
00428 }
00429
00430
00431
00432 L4_INLINE
00433 long l4_msgtag_label(l4_msgtag_t t) L4_NOTHROW
00434 {
00435     #if defined(__cplusplus) && (__cplusplus >= 202002L)
00436         return t.raw >> 16;
00437     #else
00438         return t.raw < 0 ? ~(~t.raw >> 16) : t.raw >> 16;
00439     #endif
00440 }
00441
00442 L4_INLINE
00443 unsigned l4_msgtag_words(l4_msgtag_t t) L4_NOTHROW
00444 { return t.raw & 0x3f; }
00445
00446 L4_INLINE
00447 unsigned l4_msgtag_items(l4_msgtag_t t) L4_NOTHROW
00448 { return (t.raw >> 6) & 0x3f; }
00449
00450 L4_INLINE
00451 unsigned l4_msgtag_flags(l4_msgtag_t t) L4_NOTHROW
00452 { return t.raw & 0xf000; }
00453
00454
00455 L4_INLINE
00456 unsigned l4_msgtag_has_error(l4_msgtag_t t) L4_NOTHROW
00457 { return t.raw & L4_MSGTAG_ERROR; }
00458
00459
00460

```

```

00461 L4_INLINE unsigned l4_msgtag_is_page_fault(l4_msgtag_t t) L4_NOTHROW
00462 { return l4_msgtag_label(t) == L4_PROTO_PAGE_FAULT; }
00463
00464 L4_INLINE unsigned l4_msgtag_is_exception(l4_msgtag_t t) L4_NOTHROW
00465 { return l4_msgtag_label(t) == L4_PROTO_EXCEPTION; }
00466
00467 L4_INLINE unsigned l4_msgtag_is_sigma0(l4_msgtag_t t) L4_NOTHROW
00468 { return l4_msgtag_label(t) == L4_PROTO_SIGMA0; }
00469
00470 L4_INLINE unsigned l4_msgtag_is_io_page_fault(l4_msgtag_t t) L4_NOTHROW
00471 { return l4_msgtag_label(t) == L4_PROTO_IO_PAGE_FAULT; }
00472
00473 L4_INLINE l4_cap_idx_t l4_capability_next(l4_cap_idx_t c) L4_NOTHROW
00474 { return c + L4_CAP_OFFSET; }
00475
00476 #include <l4/sys/__l4_fpage.h>
00477 #include <l4/sys/__timeout.h>


```

## 16.598 amd64/l4/sys/arch/utcb.h File Reference

UTCB definitions for AMD64.

```
#include <l4/sys/types.h>
```

Include dependency graph for utcb.h:



### Data Structures

- struct `l4_exc_regs_t`  
*UTCB structure for exceptions.*

### Functions

- `l4_umword_t l4_utcb_exc_pc(l4_exc_regs_t const *u) L4_NOTHROW`  
*Access function to get the program counter of the exception state.*
- `void l4_utcb_exc_pc_set(l4_exc_regs_t *u, l4_addr_t pc) L4_NOTHROW`  
*Set the program counter register in the exception state.*



- [l4\\_umword\\_t l4\\_utcb\\_exc\\_typeval \(l4\\_exc\\_regs\\_t const \\*u\) L4\\_NOTHROW](#)  
*Get the value out of an exception UTCB that describes the type of exception.*
- [int l4\\_utcb\\_exc\\_is\\_pf \(l4\\_exc\\_regs\\_t const \\*u\) L4\\_NOTHROW](#)  
*Check whether an exception IPC is a page fault.*
- [l4\\_addr\\_t l4\\_utcb\\_exc\\_pfa \(l4\\_exc\\_regs\\_t const \\*u\) L4\\_NOTHROW](#)  
*Function to get the L4 style page fault address out of an exception.*
- [int l4\\_utcb\\_exc\\_is\\_ex\\_regs\\_exception \(l4\\_exc\\_regs\\_t const \\*u\) L4\\_NOTHROW](#)  
*Check whether an exception IPC was triggered via [l4\\_thread\\_ex\\_regs\(\)](#).*

## 16.598.1 Detailed Description

UTCB definitions for AMD64.

Definition in file [utcb.h](#).

## 16.599 utcb.h

[Go to the documentation of this file.](#)

```

00001
00006 /*
00007  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00008  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00009  *      economic rights: Technische Universität Dresden (Germany)
00010  *
00011  * License: see LICENSE.spdx (in this directory or the directories above)
00012  */
00013 /*****
00014  *ifndef __L4_SYS__INCLUDE__ARCH_AMD64__UTCB_H__
00015  *define __L4_SYS__INCLUDE__ARCH_AMD64__UTCB_H__
00016  *
00017  *include <l4/sys/types.h>
00018  *
00023
00024 #define L4_UTCB_EXCEPTION_REGS_SIZE      26
00025 #define L4_UTCB_GENERIC_DATA_SIZE        63
00026 #define L4_UTCB_GENERIC_BUFFERS_SIZE     58
00027
00028 #define L4_UTCB_MSG_REGS_OFFSET           0
00029 #define L4_UTCB_BUF_REGS_OFFSET          (64 * sizeof(l4_umword_t))
00030 #define L4_UTCB_THREAD_REGS_OFFSET       (123 * sizeof(l4_umword_t))
00031
00032 #define L4_UTCB_INHERIT_FPU               (1UL < 24)
00033 #define L4_UTCB_OFFSET                   1024
00034
00039 struct l4_exc_regs_t
00040 {
00041     l4_umword_t r15;
00042     l4_umword_t r14;
00043     l4_umword_t r13;
00044     l4_umword_t r12;
00045     l4_umword_t r11;
00046     l4_umword_t r10;
00047     l4_umword_t r9;
00048     l4_umword_t r8;
00049     l4_umword_t rdi;
00050     l4_umword_t rsi;
00051     l4_umword_t rbp;
00052     l4_umword_t pfa;
00053     l4_umword_t rbx;
00054     l4_umword_t rdx;
00055     l4_umword_t rcx;
00056     l4_umword_t rax;
00057
00058     l4_umword_t trapno;
00059     l4_umword_t err;
00060     l4_umword_t ip;
00061     l4_umword_t dummy1;
00062     l4_umword_t flags;
00063     l4_umword_t sp;
00064     l4_umword_t ss;

```

```

00065  l4_umword_t fs_base;
00066  l4_umword_t gs_base;
00067  l4_uint16_t ds, es, fs, gs;
00068 };
00069
00070
00071 /*
00072  * =====
00073  * Implementations.
00074  */
00075
00076 L4_INLINE l4_utcb_t *l4_utcb_direct(void) L4_NOTHROW
00077 {
00078     l4_utcb_t *res;
00079     __asm__ ( "mov %%gs:0, %0 \n" : "=r"(res));
00080     return res;
00081 }
00082
00083 L4_INLINE l4_umword_t l4_utcb_exc_pc(l4_exc_regs_t const *u) L4_NOTHROW
00084 {
00085     return u->ip;
00086 }
00087
00088 L4_INLINE void l4_utcb_exc_pc_set(l4_exc_regs_t *u, l4_addr_t pc) L4_NOTHROW
00089 {
00090     u->ip = pc;
00091 }
00092
00093 L4_INLINE l4_umword_t l4_utcb_exc_typeval(l4_exc_regs_t const *u) L4_NOTHROW
00094 {
00095     return u->trapno;
00096 }
00097
00098 L4_INLINE int l4_utcb_exc_is_pf(l4_exc_regs_t const *u) L4_NOTHROW
00099 {
00100     return u->trapno == 14;
00101 }
00102
00103 L4_INLINE l4_addr_t l4_utcb_exc_pfa(l4_exc_regs_t const *u) L4_NOTHROW
00104 {
00105     return (u->pfa & ~7UL) | (u->err & 2);
00106 }
00107
00108 L4_INLINE int l4_utcb_exc_is_ex_regs_exception(l4_exc_regs_t const *u) L4_NOTHROW
00109 {
00110     return l4_utcb_exc_typeval(u) == 0xff;
00111 }
00112
00113 #endif /* ! __L4_SYS__INCLUDE__ARCH_AMD64__UTCB_H__ */


```

## 16.600 arm/l4/sys/arch/utcb.h File Reference

UTCB definitions for ARM.

```
#include <l4/sys/types.h>
```

Include dependency graph for utcb.h:



## Data Structures

- struct [l4\\_exc\\_regs\\_t](#)  
*UTCB structure for exceptions.*

## Functions

- [l4\\_umword\\_t l4\\_utcb\\_exc\\_pc](#) ([l4\\_exc\\_regs\\_t](#) const \*u) [L4\\_NOTHROW](#)  
*Access function to get the program counter of the exception state.*
- void [l4\\_utcb\\_exc\\_pc\\_set](#) ([l4\\_exc\\_regs\\_t](#) \*u, [l4\\_addr\\_t](#) pc) [L4\\_NOTHROW](#)  
*Set the program counter register in the exception state.*
- [l4\\_umword\\_t l4\\_utcb\\_exc\\_typeval](#) ([l4\\_exc\\_regs\\_t](#) const \*u) [L4\\_NOTHROW](#)  
*Get the value out of an exception UTCB that describes the type of exception.*
- int [l4\\_utcb\\_exc\\_is\\_pf](#) ([l4\\_exc\\_regs\\_t](#) const \*u) [L4\\_NOTHROW](#)  
*Check whether an exception IPC is a page fault.*
- [l4\\_addr\\_t l4\\_utcb\\_exc\\_pfa](#) ([l4\\_exc\\_regs\\_t](#) const \*u) [L4\\_NOTHROW](#)  
*Function to get the L4 style page fault address out of an exception.*
- int [l4\\_utcb\\_exc\\_is\\_ex\\_regs\\_exception](#) ([l4\\_exc\\_regs\\_t](#) const \*u) [L4\\_NOTHROW](#)  
*Check whether an exception IPC was triggered via [l4\\_thread\\_ex\\_regs\(\)](#).*

## 16.600.1 Detailed Description

UTCB definitions for ARM.

Definition in file [utcb.h](#).

## 16.601 utcb.h

[Go to the documentation of this file.](#)

```

00001
00006 /*
00007  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00008  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00009  *      economic rights: Technische Universität Dresden (Germany)
00010  *
00011  * License: see LICENSE.spdx (in this directory or the directories above)
00012  */
00013 #ifndef __L4_SYS__INCLUDE__ARCH_ARM__UTCB_H__
00014 #define __L4_SYS__INCLUDE__ARCH_ARM__UTCB_H__
00015
00016 #include <l4/sys/types.h>
00017
00022
00027 struct l4_exc_regs_t
00028 {
00029     l4_umword_t pfa;
00030     l4_umword_t err;
00031
00032     l4_umword_t r[13];
00033     l4_umword_t sp;
00034     l4_umword_t ulr;
00035     l4_umword_t _dummy1;
00036     l4_umword_t pc;
00037     l4_umword_t cpsr;
00038     l4_umword_t tpidruro;
00039     l4_umword_t tpidrurw;
00040 };
00041
00042 #define L4_UTCB_EXCEPTION_REGS_SIZE    (sizeof(l4_exc_regs_t) / sizeof(l4_umword_t))
00043 #define L4_UTCB_GENERIC_DATA_SIZE     63
00044 #define L4_UTCB_GENERIC_BUFFERS_SIZE  58
00045
00046 #define L4_UTCB_MSG_REGS_OFFSET        0
00047 #define L4_UTCB_BUF_REGS_OFFSET        (64 * sizeof(l4_umword_t))
00048 #define L4_UTCB_THREAD_REGS_OFFSET     (123 * sizeof(l4_umword_t))
00049
00050 #define L4_UTCB_INHERIT_FPU             (1UL << 24)
00051
00052 #define L4_UTCB_OFFSET                  512
00053
00054 /*
00055  * =====
00056  * Implementations.
00057  */
00058
00059 #ifdef __GNUC__
00060 L4_INLINE l4_utcb_t *l4_utcb_direct(void) L4_NOTHROW
00061 {
00062     # if defined(__ARM_ARCH) && __ARM_ARCH >= 7
00063         l4_utcb_t *utcb;
00064         __asm__ ("mrc p15, 0, %0, c13, c0, 2" : "=r" (utcb)); // TPIDRURW
00065     #else
00066         register l4_utcb_t *utcb __asm__ ("r0");
00067         __asm__ ("mov lr, pc\n"
00068                 "mvn pc, #0xff\n"
00069                 : "=r" (utcb) : : "lr"); // write 0xffffffff00 to pc
00070     #endif
00071     return utcb;
00072 }
00073 #endif
00074
00075 L4_INLINE l4_umword_t l4_utcb_exc_pc(l4_exc_regs_t const *u) L4_NOTHROW
00076 {
00077     return u->pc;
00078 }
00079
00080 L4_INLINE void l4_utcb_exc_pc_set(l4_exc_regs_t *u, l4_addr_t pc) L4_NOTHROW
00081 {
00082     u->pc = pc;
00083 }
00084
00085 L4_INLINE l4_umword_t l4_utcb_exc_typeval(l4_exc_regs_t const *u) L4_NOTHROW
00086 {
00087     return u->err >> 26;
00088 }
00089
00090 L4_INLINE int l4_utcb_exc_is_pf(l4_exc_regs_t const *u) L4_NOTHROW
00091 {
00092     return ((u->err >> 26) & 0x30) == 0x20;
00093 }
00094

```

```

00095 L4_INLINE l4_addr_t l4_utcb_exc_pfa(l4_exc_regs_t const *u) L4_NOTHROW
00096 {
00097     return (u->pfa & ~7UL) | ((u->err >> 5) & 2);
00098 }
00099
00100 L4_INLINE int l4_utcb_exc_is_ex_regs_exception(l4_exc_regs_t const *u) L4_NOTHROW
00101 {
00102     return l4_utcb_exc_typeval(u) == 0x3e;
00103 }
00104
00105 #endif /* ! __L4_SYS__INCLUDE__ARCH_ARM__UTCB_H__ */


```

## 16.602 arm64/l4/sys/arch/utcb.h File Reference

UTCB definitions for ARM64.

```
#include <l4/sys/types.h>
```

Include dependency graph for utcb.h:



### Data Structures

- struct `l4_exc_regs_t`  
UTCB structure for exceptions.

### Functions

- `l4_umword_t l4_utcb_exc_pc(l4_exc_regs_t const *u) L4_NOTHROW`  
Access function to get the program counter of the exception state.
- `void l4_utcb_exc_pc_set(l4_exc_regs_t *u, l4_addr_t pc) L4_NOTHROW`  
Set the program counter register in the exception state.
- `l4_umword_t l4_utcb_exc_typeval(l4_exc_regs_t const *u) L4_NOTHROW`  
Get the value out of an exception UTCB that describes the type of exception.
- `int l4_utcb_exc_is_pf(l4_exc_regs_t const *u) L4_NOTHROW`  
Check whether an exception IPC is a page fault.
- `l4_addr_t l4_utcb_exc_pfa(l4_exc_regs_t const *u) L4_NOTHROW`  
Function to get the L4 style page fault address out of an exception.
- `int l4_utcb_exc_is_ex_regs_exception(l4_exc_regs_t const *u) L4_NOTHROW`  
Check whether an exception IPC was triggered via `l4_thread_ex_regs()`.

## 16.602.1 Detailed Description

UTCB definitions for ARM64.

Definition in file [utcb.h](#).

## 16.603 utcb.h

[Go to the documentation of this file.](#)

```

00001
00006 /*
00007  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00008  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00009  *      economic rights: Technische Universität Dresden (Germany)
00010  *
00011  * License: see LICENSE.spdx (in this directory or the directories above)
00012  */
00013 #ifndef __L4_SYS__INCLUDE__ARCH_ARM64__UTCB_H__
00014 #define __L4_SYS__INCLUDE__ARCH_ARM64__UTCB_H__
00015
00016 #include <l4/sys/types.h>
00017
00022
00027 struct l4_exc_regs_t
00028 {
00029     l4_umword_t eret_work;
00030     l4_umword_t r[31];
00031     l4_umword_t reserved;
00032     l4_umword_t err;
00033
00034     l4_umword_t pfa;
00035     l4_umword_t sp;
00036     union { l4_umword_t ip; l4_umword_t pc; }; /* aliases for PC */
00037     union { l4_umword_t flags; l4_umword_t pstate; }; /* aliases for PSTATE (PSR) */
00038     l4_umword_t tpidrro;
00039     l4_umword_t tpidrurw;
00040 };
00041
00042 #define L4_UTCB_EXCEPTION_REGS_SIZE    (sizeof(l4_exc_regs_t) / sizeof(l4_umword_t))
00043 #define L4_UTCB_GENERIC_DATA_SIZE      63
00044 #define L4_UTCB_GENERIC_BUFFERS_SIZE   58
00045
00046 #define L4_UTCB_MSG_REGS_OFFSET         0
00047 #define L4_UTCB_BUF_REGS_OFFSET         (64 * sizeof(l4_umword_t))
00048 #define L4_UTCB_THREAD_REGS_OFFSET      (123 * sizeof(l4_umword_t))
00049
00050 #define L4_UTCB_INHERIT_FPU              (1UL << 24)
00051
00052 #define L4_UTCB_OFFSET                  1024
00053
00054 /*
00055  * =====
00056  * Implementations.
00057  */
00058
00059 #ifndef __GNUC__
00060 L4_INLINE l4_utcb_t *l4_utcb_direct(void) L4_NOTHROW
00061 {
00062     l4_utcb_t *utcb;
00063     __asm__ ("mrs %0, TPIDRRO_EL0" : "=r" (utcb));
00064     return utcb;
00065 }
00066 #endif
00067
00068 L4_INLINE l4_umword_t l4_utcb_exc_pc(l4_exc_regs_t const *u) L4_NOTHROW
00069 {
00070     return u->pc;
00071 }
00072
00073 L4_INLINE void l4_utcb_exc_pc_set(l4_exc_regs_t *u, l4_addr_t pc) L4_NOTHROW
00074 {
00075     u->pc = pc;
00076 }
00077
00078 L4_INLINE l4_umword_t l4_utcb_exc_typeval(l4_exc_regs_t const *u) L4_NOTHROW
00079 {
00080     return u->err >> 26;
00081 }

```

```

00082
00083 L4_INLINE int l4_utcb_exc_is_pf(l4_exc_regs_t const *u) L4_NOTHROW
00084 {
00085     return ((u->err >> 26) & 0x30) == 0x20;
00086 }
00087
00088 L4_INLINE l4_addr_t l4_utcb_exc_pfa(l4_exc_regs_t const *u) L4_NOTHROW
00089 {
00090     return (u->pfa & ~7UL) | ((u->err >> 5) & 2);
00091 }
00092
00093 L4_INLINE int l4_utcb_exc_is_ex_regs_exception(l4_exc_regs_t const *u) L4_NOTHROW
00094 {
00095     return (u->err >> 26) == 0x3e;
00096 }
00097
00098 #endif /* ! __L4_SYS__INCLUDE__ARCH_ARM64__UTCB_H__ */

```

## 16.604 l4/sys/utcb.h File Reference


UTCB definitions.

```


#include <l4/sys/types.h>
#include <l4/sys/compiler.h>
#include <l4/sys/l4int.h>
#include <l4/sys/arch/utcb.h>

```

Include dependency graph for utcb.h:



This graph shows which files directly or indirectly include this file:



### Data Structures

- union [l4\\_msg\\_regs\\_t](#)  
*Encapsulation of the message-register block in the UTCB.*
- struct [l4\\_buf\\_regs\\_t](#)  
*Encapsulation of the buffer-registers block in the UTCB.*
- struct [l4\\_thread\\_regs\\_t](#)  
*Encapsulation of the thread-control-register block of the UTCB.*

## Typedefs

- typedef struct [l4\\_utcb\\_t](#) [l4\\_utcb\\_t](#)  
*Opaque type for the UTCB.*
- typedef union [l4\\_msg\\_regs\\_t](#) [l4\\_msg\\_regs\\_t](#)  
*Encapsulation of the message-register block in the UTCB.*
- typedef struct [l4\\_buf\\_regs\\_t](#) [l4\\_buf\\_regs\\_t](#)  
*Encapsulation of the buffer-registers block in the UTCB.*
- typedef struct [l4\\_thread\\_regs\\_t](#) [l4\\_thread\\_regs\\_t](#)  
*Encapsulation of the thread-control-register block of the UTCB.*

## Functions

- [l4\\_umword\\_t](#) [l4\\_utcb\\_exc\\_pc](#) ([l4\\_exc\\_regs\\_t](#) const \*u) [L4\\_NOTHROW](#) [L4\\_PURE](#)  
*Access function to get the program counter of the exception state.*
- void [l4\\_utcb\\_exc\\_pc\\_set](#) ([l4\\_exc\\_regs\\_t](#) \*u, [l4\\_addr\\_t](#) pc) [L4\\_NOTHROW](#)  
*Set the program counter register in the exception state.*
- unsigned long [l4\\_utcb\\_exc\\_typeval](#) ([l4\\_exc\\_regs\\_t](#) const \*u) [L4\\_NOTHROW](#) [L4\\_PURE](#)  
*Get the value out of an exception UTCB that describes the type of exception.*
- int [l4\\_utcb\\_exc\\_is\\_pf](#) ([l4\\_exc\\_regs\\_t](#) const \*u) [L4\\_NOTHROW](#) [L4\\_PURE](#)  
*Check whether an exception IPC is a page fault.*
- [l4\\_addr\\_t](#) [l4\\_utcb\\_exc\\_pfa](#) ([l4\\_exc\\_regs\\_t](#) const \*u) [L4\\_NOTHROW](#) [L4\\_PURE](#)  
*Function to get the [L4](#) style page fault address out of an exception.*
- int [l4\\_utcb\\_exc\\_is\\_ex\\_regs\\_exception](#) ([l4\\_exc\\_regs\\_t](#) const \*u) [L4\\_NOTHROW](#) [L4\\_PURE](#)  
*Check whether an exception IPC was triggered via [l4\\_thread\\_ex\\_regs\(\)](#).*
- [l4\\_utcb\\_t](#) \* [l4\\_utcb](#) (void) [L4\\_NOTHROW](#) [L4\\_PURE](#)  
*Get the UTCB address.*
- [l4\\_msg\\_regs\\_t](#) \* [l4\\_utcb\\_mr](#) (void) [L4\\_NOTHROW](#) [L4\\_PURE](#)  
*Get the message-register block of a UTCB.*
- [l4\\_buf\\_regs\\_t](#) \* [l4\\_utcb\\_br](#) (void) [L4\\_NOTHROW](#) [L4\\_PURE](#)  
*Get the buffer-register block of a UTCB.*
- [l4\\_thread\\_regs\\_t](#) \* [l4\\_utcb\\_tcr](#) (void) [L4\\_NOTHROW](#) [L4\\_PURE](#)  
*Get the thread-control-register block of a UTCB.*
- [l4\\_exc\\_regs\\_t](#) \* [l4\\_utcb\\_exc](#) (void) [L4\\_NOTHROW](#) [L4\\_PURE](#)  
*Get the message-register block of a UTCB (for an exception IPC).*
- void [l4\\_utcb\\_inherit\\_fpu](#) (int switch\_on) [L4\\_NOTHROW](#)  
*Enable or disable inheritance of FPU state to receiver.*
- [l4\\_timeout\\_s](#) [l4\\_timeout\\_abs](#) ([l4\\_kernel\\_clock\\_t](#) pint, int br) [L4\\_NOTHROW](#)  
*Set an absolute timeout.*
- unsigned [l4\\_utcb\\_mr64\\_idx](#) (unsigned idx) [L4\\_NOTHROW](#)  
*Get index into 64bit message registers alias from native-sized index.*

### 16.604.1 Detailed Description

UTCB definitions.

Definition in file [utcb.h](#).



## 16.605 utcb.h

[Go to the documentation of this file.](#)

```

00001 /*****
00002  */
00003 * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00004 *      Alexander Warg <warg@os.inf.tu-dresden.de>,
00005 *      Torsten Frenzel <frenzel@os.inf.tu-dresden.de>
00006 *      economic rights: Technische Universität Dresden (Germany)
00007 *
00008 * License: see LICENSE.spdx (in this directory or the directories above)
00009 */
00010 /*****
00011  */
00012 #ifndef _L4_SYS_UTCB_H
00013 #define _L4_SYS_UTCB_H
00014
00015 #include <l4/sys/types.h>
00016 #include <l4/sys/compiler.h>
00017 #include <l4/sys/l4int.h>
00018
00019 typedef struct l4_utcb_t l4_utcb_t;
00020
00021 typedef struct l4_exc_regs_t l4_exc_regs_t;
00022
00023 L4_INLINE l4_utcb_t *l4_utcb_direct(void) L4_NOTHROW L4_PURE;
00024
00025 L4_INLINE l4_umword_t l4_utcb_exc_pc(l4_exc_regs_t const *u) L4_NOTHROW L4_PURE;
00026
00027 L4_INLINE void l4_utcb_exc_pc_set(l4_exc_regs_t *u, l4_addr_t pc) L4_NOTHROW;
00028
00029 L4_INLINE unsigned long l4_utcb_exc_typeval(l4_exc_regs_t const *u) L4_NOTHROW L4_PURE;
00030
00031 L4_INLINE int l4_utcb_exc_is_pf(l4_exc_regs_t const *u) L4_NOTHROW L4_PURE;
00032
00033 L4_INLINE l4_addr_t l4_utcb_exc_pfa(l4_exc_regs_t const *u) L4_NOTHROW L4_PURE;
00034
00035 L4_INLINE int l4_utcb_exc_is_ex_regs_exception(l4_exc_regs_t const *u) L4_NOTHROW L4_PURE;
00036
00037 #include <l4/sys/arch/utcb.h>
00038
00039 typedef union l4_msg_regs_t
00040 {
00041     l4_umword_t mr[L4_UTCB_GENERIC_DATA_SIZE];
00042     l4_uint64_t mr64[L4_UTCB_GENERIC_DATA_SIZE / (sizeof(l4_uint64_t)/sizeof(l4_umword_t))];
00043 } l4_msg_regs_t;
00044
00045 typedef struct l4_buf_regs_t
00046 {
00047     l4_umword_t bdr;
00048
00049     l4_umword_t br[L4_UTCB_GENERIC_BUFFERS_SIZE];
00050 } l4_buf_regs_t;
00051
00052 typedef struct l4_thread_regs_t
00053 {
00054     l4_umword_t error;
00055
00056     l4_umword_t free_marker;
00057
00058     l4_umword_t user[3];
00059 } l4_thread_regs_t;
00060
00061 L4_BEGIN_DECLS
00062
00063 L4_CV l4_utcb_t *l4_utcb_wrap(void) L4_NOTHROW L4_PURE;
00064
00065 L4_INLINE l4_utcb_t *l4_utcb(void) L4_NOTHROW L4_PURE;
00066
00067 L4_INLINE l4_msg_regs_t *l4_utcb_mr(void) L4_NOTHROW L4_PURE;
00068
00069 L4_INLINE l4_msg_regs_t *l4_utcb_mr_u(l4_utcb_t *u) L4_NOTHROW L4_PURE;
00070
00071 L4_INLINE l4_buf_regs_t *l4_utcb_br(void) L4_NOTHROW L4_PURE;
00072
00073 L4_INLINE l4_buf_regs_t *l4_utcb_br_u(l4_utcb_t *u) L4_NOTHROW L4_PURE;
00074
00075 L4_INLINE l4_thread_regs_t *l4_utcb_tcr(void) L4_NOTHROW L4_PURE;
00076
00077 L4_INLINE l4_thread_regs_t *l4_utcb_tcr_u(l4_utcb_t *u) L4_NOTHROW L4_PURE;
00078
00079 L4_INLINE l4_exc_regs_t *l4_utcb_exc(void) L4_NOTHROW L4_PURE;
00080
00081

```

```

00269 L4_INLINE l4_exc_regs_t *l4_utcb_exc_u(l4_utcb_t *u) L4_NOTHROW L4_PURE;
00270
00275 L4_INLINE void l4_utcb_inherit_fpu(int switch_on) L4_NOTHROW;
00276
00280 L4_INLINE void l4_utcb_inherit_fpu_u(l4_utcb_t *u, int switch_on) L4_NOTHROW;
00281
00296 L4_INLINE
00297 l4_timeout_s l4_timeout_abs_u(l4_kernel_clock_t pint, int br,
00298                               l4_utcb_t *utcb) L4_NOTHROW;
00312 L4_INLINE
00313 l4_timeout_s l4_timeout_abs(l4_kernel_clock_t pint, int br) L4_NOTHROW;
00314
00322 L4_INLINE
00323 unsigned l4_utcb_mr64_idx(unsigned idx) L4_NOTHROW;
00324
00325 /*****
00326  * Implementations
00327  *****/
00328
00329 L4_INLINE l4_msg_regs_t *l4_utcb_mr_u(l4_utcb_t *u) L4_NOTHROW
00330 { return (l4_msg_regs_t*)((char*)u + L4_UTCB_MSG_REGS_OFFSET); }
00331
00332 L4_INLINE l4_buf_regs_t *l4_utcb_br_u(l4_utcb_t *u) L4_NOTHROW
00333 { return (l4_buf_regs_t*)((char*)u + L4_UTCB_BUF_REGS_OFFSET); }
00334
00335 L4_INLINE l4_thread_regs_t *l4_utcb_tcr_u(l4_utcb_t *u) L4_NOTHROW
00336 { return (l4_thread_regs_t*)((char*)u + L4_UTCB_THREAD_REGS_OFFSET); }
00337
00338 L4_INLINE l4_exc_regs_t *l4_utcb_exc_u(l4_utcb_t *u) L4_NOTHROW
00339 { return (l4_exc_regs_t*)((char*)u + L4_UTCB_MSG_REGS_OFFSET); }
00340
00341 L4_INLINE void l4_utcb_inherit_fpu_u(l4_utcb_t *u, int switch_on) L4_NOTHROW
00342 {
00343     if (switch_on)
00344         l4_utcb_br_u(u)->bdr |= L4_UTCB_INHERIT_FPU;
00345     else
00346         l4_utcb_br_u(u)->bdr &= ~L4_UTCB_INHERIT_FPU;
00347 }
00348
00349 L4_INLINE l4_utcb_t *l4_utcb(void) L4_NOTHROW
00350 {
00351     #ifdef L4SYS_USE_UTCB_WRAP
00352         return l4_utcb_wrap();
00353     #else
00354         return l4_utcb_direct();
00355     #endif
00356 }
00357
00358
00359
00360
00361 L4_INLINE l4_msg_regs_t *l4_utcb_mr(void) L4_NOTHROW
00362 { return l4_utcb_mr_u(l4_utcb()); }
00363
00364 L4_INLINE l4_buf_regs_t *l4_utcb_br(void) L4_NOTHROW
00365 { return l4_utcb_br_u(l4_utcb()); }
00366
00367 L4_INLINE l4_thread_regs_t *l4_utcb_tcr(void) L4_NOTHROW
00368 { return l4_utcb_tcr_u(l4_utcb()); }
00369
00370 L4_INLINE l4_exc_regs_t *l4_utcb_exc(void) L4_NOTHROW
00371 { return l4_utcb_exc_u(l4_utcb()); }
00372
00373 L4_INLINE void l4_utcb_inherit_fpu(int switch_on) L4_NOTHROW
00374 { l4_utcb_inherit_fpu_u(l4_utcb(), switch_on); }
00375
00376 L4_INLINE
00377 l4_timeout_s l4_timeout_abs_u(l4_kernel_clock_t val, int pos,
00378                               l4_utcb_t *utcb) L4_NOTHROW
00379 {
00380     union T
00381     {
00382         l4_kernel_clock_t t;
00383         l4_umword_t m[sizeof(l4_kernel_clock_t)/sizeof(l4_umword_t)];
00384     };
00385     l4_timeout_s to;
00386     to.t = 0x8000 | pos;
00387     ((union T*)(l4_utcb_br_u(utcb)->br + pos))->t = val;
00388     return to;
00389 }
00390
00391 L4_INLINE
00392 l4_timeout_s l4_timeout_abs(l4_kernel_clock_t val, int pos) L4_NOTHROW
00393 { return l4_timeout_abs_u(val, pos, l4_utcb()); }
00394
00395 L4_INLINE unsigned l4_utcb_mr64_idx(unsigned idx) L4_NOTHROW
00396 { return idx / (sizeof(l4_uint64_t) / sizeof(l4_umword_t)); }

```

```

00397
00398 L4_END_DECLS
00399
00400 #endif /* ! _L4_SYS_UTCB_H */


```

## 16.606 x86/l4/sys/arch/utcb.h File Reference

UTCB definitions for x86.

```
#include <l4/sys/types.h>
```

Include dependency graph for utcb.h:



### Data Structures

- struct `l4_exc_regs_t`  
*UTCB structure for exceptions.*

### Macros

- `#define L4_UTCB_EXCEPTION_REGS_SIZE 19`  
*Number of message registers used for exception IPC.*
- `#define L4_UTCB_GENERIC_DATA_SIZE 63`  
*Total number of message register (MRs) available.*
- `#define L4_UTCB_GENERIC_BUFFERS_SIZE 58`  
*Total number of buffer registers (BRs) available.*
- `#define L4_UTCB_MSG_REGS_OFFSET 0`  
*Offset of MR[0] relative to the UTCB pointer.*
- `#define L4_UTCB_BUF_REGS_OFFSET (64 * sizeof(l4_umword_t))`  
*Offset of BR[0] relative to the UTCB pointer.*
- `#define L4_UTCB_THREAD_REGS_OFFSET (123 * sizeof(l4_umword_t))`  
*Offset of TCR[0] relative to the UTCB pointer.*
- `#define L4_UTCB_INHERIT_FPU (1UL << 24)`  
*BDR flag to accept reception of FPU state.*
- `#define L4_UTCB_OFFSET 512`  
*Offset of two consecutive UTCBs.*



```

00064     l4_umword_t ebx;
00065     l4_umword_t edx;
00066     l4_umword_t ecx;
00067     l4_umword_t eax;
00068
00069     l4_umword_t trapno;
00070     l4_umword_t err;
00071
00072     l4_umword_t ip;
00073     l4_umword_t dummy1;
00074     l4_umword_t flags;
00075     l4_umword_t sp;
00076     l4_umword_t ss;
00077 };
00078
00079 /*
00080  * =====
00081  * Implementations.
00082  */
00083
00084 L4_INLINE l4_utcb_t *l4_utcb_direct(void) L4_NOTHROW
00085 {
00086     l4_utcb_t *utcb;
00087     __asm__ ("mov %%fs:0, %0" : "=r" (utcb));
00088     return utcb;
00089 }
00090
00091 L4_INLINE l4_umword_t l4_utcb_exc_pc(l4_exc_regs_t const *u) L4_NOTHROW
00092 {
00093     return u->ip;
00094 }
00095
00096 L4_INLINE void l4_utcb_exc_pc_set(l4_exc_regs_t *u, l4_addr_t pc) L4_NOTHROW
00097 {
00098     u->ip = pc;
00099 }
00100
00101 L4_INLINE void l4_utcb_exc_sp_set(l4_exc_regs_t *u, l4_addr_t sp) L4_NOTHROW
00102 {
00103     u->sp = sp;
00104 }
00105
00106 L4_INLINE l4_umword_t l4_utcb_exc_typeval(l4_exc_regs_t const *u) L4_NOTHROW
00107 {
00108     return u->trapno;
00109 }
00110
00111 L4_INLINE int l4_utcb_exc_is_pf(l4_exc_regs_t const *u) L4_NOTHROW
00112 {
00113     return u->trapno == 14;
00114 }
00115
00116 L4_INLINE l4_addr_t l4_utcb_exc_pfa(l4_exc_regs_t const *u) L4_NOTHROW
00117 {
00118     return (u->pfa & ~7UL) | (u->err & 2);
00119 }
00120
00121 L4_INLINE int l4_utcb_exc_is_ex_regs_exception(l4_exc_regs_t const *u) L4_NOTHROW
00122 {
00123     return l4_utcb_exc_typeval(u) == 0xff;
00124 }
00125
00126 #endif /* ! __L4_SYS__INCLUDE__ARCH_X86__UTCB_H__ */

```

## 16.608 l4/sys/vcon File Reference


C++ Virtual console interface.

```


#include <l4/sys/icu>
#include <l4/sys/vcon.h>
#include <l4/sys/capability>

```

Include dependency graph for vcon:



This graph shows which files directly or indirectly include this file:



## Data Structures

- class `L4::Vcon`  
*C++ L4 Vcon interface, see [Virtual Console](#) for the C interface.*

## Namespaces

- namespace **L4**  
*L4 low-level kernel interface.*

## 16.608.1 Detailed Description

C++ Virtual console interface.

Definition in file [vcon](#).

## 16.609 vcon

[Go to the documentation of this file.](#)

```


00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00002 /*
00003  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00004  *      Alexander Warg <warg@os.inf.tu-dresden.de>,
00005  *      Torsten Frenzel <frenzel@os.inf.tu-dresden.de>
00006  *      economic rights: Technische Universität Dresden (Germany)
00007  *
00008  * License: see LICENSE.spdx (in this directory or the directories above)
00009  */
00010 #pragma once
00011
00012 #include <l4/sys/icu>
00013 #include <l4/sys/vcon.h>
00014 #include <l4/sys/capability>
00015
00016 namespace L4 {
00017
00018 class Vcon :
00019     public Kobject_t<Vcon, Icu, L4_PROTO_LOG>
00020 {
00021 public:
00022     l4_msgtag_t
00023     send(char const *buf, unsigned size, l4_utcb_t *utcb = l4_utcb()) const noexcept
00024     { return l4_vcon_send_u(cap(), buf, size, utcb); }
00025
00026     long
00027     write(char const *buf, unsigned size, l4_utcb_t *utcb = l4_utcb()) const noexcept
00028     { return l4_vcon_write_u(cap(), buf, size, utcb); }
00029
00030     int
00031     read(char *buf, unsigned size, l4_utcb_t *utcb = l4_utcb()) const noexcept
00032     { return l4_vcon_read_u(cap(), buf, size, utcb); }
00033
00034     int
00035     read_with_flags(char *buf, unsigned size, l4_utcb_t *utcb = l4_utcb()) const noexcept
00036     { return l4_vcon_read_with_flags_u(cap(), buf, size, utcb); }
00037
00038     l4_msgtag_t
00039     set_attr(l4_vcon_attr_t const *attr, l4_utcb_t *utcb = l4_utcb()) const noexcept
00040     { return l4_vcon_set_attr_u(cap(), attr, utcb); }
00041
00042     l4_msgtag_t
00043     get_attr(l4_vcon_attr_t *attr, l4_utcb_t *utcb = l4_utcb()) const noexcept
00044     { return l4_vcon_get_attr_u(cap(), attr, utcb); }
00045
00046     typedef L4::Typeid::Raw_ipc<Vcon> Rpcs;
00047 };
00048
00049 }
```

## 16.610 l4/sys/vcon.h File Reference


Virtual console interface.

```
#include <l4/sys/ipc.h>
```

Include dependency graph for vcon.h:



This graph shows which files directly or indirectly include this file:



## Data Structures

- struct `l4_vcon_attr_t`  
*Vcon attribute structure.*

## Typedefs

- typedef struct `l4_vcon_attr_t` `l4_vcon_attr_t`  
*Vcon attribute structure.*



## Enumerations

- enum `L4_vcon_size_consts` { `L4_VCON_WRITE_SIZE` = (L4\_UTCB\_GENERIC\_DATA\_SIZE - 2) \* sizeof(l4\_umword\_t) , `L4_VCON_READ_SIZE` = (L4\_UTCB\_GENERIC\_DATA\_SIZE - 1) \* sizeof(l4\_umword\_t) }  
*Size constants.*
- enum `L4_vcon_read_flags` { `L4_VCON_READ_SIZE_MASK` = 0x3ffffff , `L4_VCON_READ_STAT_BREAK` = 1 << 30 , `L4_VCON_READ_STAT_DONE` = 1 << 31 }  
*Vcon read flags.*
- enum `L4_vcon_i_flags` { `L4_VCON_INLCR` = 000100 , `L4_VCON_IGNCR` = 000200 , `L4_VCON_ICRNL` = 000400 }  
*Input flags.*
- enum `L4_vcon_o_flags` { `L4_VCON_ONLCR` = 000004 , `L4_VCON_OCRNL` = 000010 , `L4_VCON_ONLRET` = 000040 }  
*Output flags.*
- enum `L4_vcon_l_flags` { `L4_VCON_ICANON` = 000002 , `L4_VCON_ECHO` = 000010 }  
*Local flags.*
- enum `L4_vcon_ops` { `L4_VCON_WRITE_OP` = 0UL , `L4_VCON_READ_OP` = 1UL , `L4_VCON_SET_ATTR_OP` = 2UL , `L4_VCON_GET_ATTR_OP` = 3UL }  
*Operations on vcon objects.*

## Functions

- `l4_msgtag_t l4_vcon_send` (l4\_cap\_idx\_t vcon, char const \*buf, unsigned size) `L4_NOTHROW`  
*Send data to virtual console.*
- `l4_msgtag_t l4_vcon_send_u` (l4\_cap\_idx\_t vcon, char const \*buf, unsigned size, l4\_utcb\_t \*utcb) `L4_NOTHROW`  
*Send data to *this* virtual console.*
- `long l4_vcon_write` (l4\_cap\_idx\_t vcon, char const \*buf, unsigned size) `L4_NOTHROW`  
*Write data to virtual console.*
- `long l4_vcon_write_u` (l4\_cap\_idx\_t vcon, char const \*buf, unsigned size, l4\_utcb\_t \*utcb) `L4_NOTHROW`  
*Write data to *this* virtual console.*
- `int l4_vcon_read` (l4\_cap\_idx\_t vcon, char \*buf, unsigned size) `L4_NOTHROW`  
*Read data from virtual console.*
- `int l4_vcon_read_u` (l4\_cap\_idx\_t vcon, char \*buf, unsigned size, l4\_utcb\_t \*utcb) `L4_NOTHROW`  
*Read data from *this* virtual console.*
- `int l4_vcon_read_with_flags` (l4\_cap\_idx\_t vcon, char \*buf, unsigned size) `L4_NOTHROW`  
*Read data from virtual console, extended version including flags.*
- `l4_msgtag_t l4_vcon_set_attr` (l4\_cap\_idx\_t vcon, l4\_vcon\_attr\_t const \*attr) `L4_NOTHROW`  
*Set attributes of a Vcon.*
- `l4_msgtag_t l4_vcon_set_attr_u` (l4\_cap\_idx\_t vcon, l4\_vcon\_attr\_t const \*attr, l4\_utcb\_t \*utcb) `L4_NOTHROW`  
*Set the attributes of *this* virtual console.*
- `l4_msgtag_t l4_vcon_get_attr` (l4\_cap\_idx\_t vcon, l4\_vcon\_attr\_t \*attr) `L4_NOTHROW`  
*Get attributes of a Vcon.*
- `l4_msgtag_t l4_vcon_get_attr_u` (l4\_cap\_idx\_t vcon, l4\_vcon\_attr\_t \*attr, l4\_utcb\_t \*utcb) `L4_NOTHROW`  
*Get attributes of *this* virtual console.*
- `void l4_vcon_set_attr_raw` (l4\_vcon\_attr\_t \*attr) `L4_NOTHROW`  
*Set terminal attributes to disable all special processing.*

## 16.610.1 Detailed Description

Virtual console interface.

Definition in file [vcon.h](#).

## 16.610.2 Enumeration Type Documentation

### 16.610.2.1 L4\_vcon\_read\_flags

```
enum L4_vcon_read_flags
```

Vcon read flags.

#### Enumerator

L4_VCON_READ_SIZE_MASK	Size mask.
L4_VCON_READ_STAT_BREAK	Break condition flag.
L4_VCON_READ_STAT_DONE	Done condition flag.

Definition at line 170 of file [vcon.h](#).

## 16.611 vcon.h

[Go to the documentation of this file.](#)

```
00001
00005 /*
00006  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00007  *      Alexander Warg <warg@os.inf.tu-dresden.de>,
00008  *      Torsten Frenzel <frenzel@os.inf.tu-dresden.de>
00009  *      economic rights: Technische Universität Dresden (Germany)
00010  *
00011  * License: see LICENSE.spdx (in this directory or the directories above)
00012  */
00013 #pragma once
00014
00015 #include <l4/sys/ipc.h>
00016
00039
00056 L4_INLINE l4_msgtag_t
00057 l4_vcon_send(l4_cap_idx_t vcon, char const *buf, unsigned size) L4_NOTHROW;
00058
00065 L4_INLINE l4_msgtag_t
00066 l4_vcon_send_u(l4_cap_idx_t vcon, char const *buf, unsigned size, l4_utcb_t *utcb) L4_NOTHROW;
00067
00079 L4_INLINE long
00080 l4_vcon_write(l4_cap_idx_t vcon, char const *buf, unsigned size) L4_NOTHROW;
00081
00088 L4_INLINE long
00089 l4_vcon_write_u(l4_cap_idx_t vcon, char const *buf, unsigned size, l4_utcb_t *utcb) L4_NOTHROW;
00090
00095 enum L4_vcon_size_consts
00096 {
00098     L4_VCON_WRITE_SIZE = (L4_UTCB_GENERIC_DATA_SIZE - 2) * sizeof(l4_umword_t),
00100     L4_VCON_READ_SIZE  = (L4_UTCB_GENERIC_DATA_SIZE - 1) * sizeof(l4_umword_t),
00101 };
00102
00119 L4_INLINE int
00120 l4_vcon_read(l4_cap_idx_t vcon, char *buf, unsigned size) L4_NOTHROW;
00121
00128 L4_INLINE int
00129 l4_vcon_read_u(l4_cap_idx_t vcon, char *buf, unsigned size, l4_utcb_t *utcb) L4_NOTHROW;
```

```

00130
00157 L4_INLINE int
00158 l4_vcon_read_with_flags(l4_cap_idx_t vcon, char *buf, unsigned size) L4_NOTHROW;
00159
00163 L4_INLINE int
00164 l4_vcon_read_with_flags_u(l4_cap_idx_t vcon, char *buf, unsigned size,
00165                           l4_utcb_t *utcb) L4_NOTHROW;
00166
00170 enum L4_vcon_read_flags
00171 {
00172     L4_VCON_READ_SIZE_MASK = 0x3fffffff,
00173     L4_VCON_READ_STAT_BREAK = 1 << 30,
00174     L4_VCON_READ_STAT_DONE = 1 << 31,
00175 };
00176
00187 typedef struct l4_vcon_attr_t
00188 {
00189     l4_umword_t i_flags;
00190     l4_umword_t o_flags;
00191     l4_umword_t l_flags;
00192
00193 #ifdef __cplusplus
00200     inline void set_raw();
00201 #endif
00202 } l4_vcon_attr_t;
00203
00208 enum L4_vcon_i_flags
00209 {
00210     L4_VCON_INLCR = 000100,
00211     L4_VCON_IGNCR = 000200,
00212     L4_VCON_ICRNL = 000400,
00213 };
00214
00219 enum L4_vcon_o_flags
00220 {
00221     L4_VCON_ONLCR = 000004,
00222     L4_VCON_OCRNL = 000010,
00223     L4_VCON_ONLRET = 000040,
00224 };
00225
00230 enum L4_vcon_l_flags
00231 {
00232     L4_VCON_ICANON = 000002,
00233     L4_VCON_ECHO = 000010,
00234 };
00235
00244 L4_INLINE l4_msgtag_t
00245 l4_vcon_set_attr(l4_cap_idx_t vcon, l4_vcon_attr_t const *attr) L4_NOTHROW;
00246
00253 L4_INLINE l4_msgtag_t
00254 l4_vcon_set_attr_u(l4_cap_idx_t vcon, l4_vcon_attr_t const *attr,
00255                   l4_utcb_t *utcb) L4_NOTHROW;
00256
00265 L4_INLINE l4_msgtag_t
00266 l4_vcon_get_attr(l4_cap_idx_t vcon, l4_vcon_attr_t *attr) L4_NOTHROW;
00267
00274 L4_INLINE l4_msgtag_t
00275 l4_vcon_get_attr_u(l4_cap_idx_t vcon, l4_vcon_attr_t *attr,
00276                   l4_utcb_t *utcb) L4_NOTHROW;
00277
00283 L4_INLINE void
00284 l4_vcon_set_attr_raw(l4_vcon_attr_t *attr) L4_NOTHROW;
00285
00286
00291 enum L4_vcon_ops
00292 {
00293     L4_VCON_WRITE_OP = 0UL,
00294     L4_VCON_READ_OP = 1UL,
00295     L4_VCON_SET_ATTR_OP = 2UL,
00296     L4_VCON_GET_ATTR_OP = 3UL,
00297 };
00298
00299 /***** Implementations *****/
00300
00301 L4_INLINE l4_msgtag_t
00302 l4_vcon_send_u(l4_cap_idx_t vcon, char const *buf, unsigned size, l4_utcb_t *utcb) L4_NOTHROW
00303 {
00304     l4_msg_regs_t *mr = l4_utcb_mr_u(utcb);
00305     mr->mr[0] = L4_VCON_WRITE_OP;
00306     mr->mr[1] = size;
00307     __builtin_memcpy(&mr->mr[2], buf, size);
00308     return l4_ipc_send(vcon, utcb,
00309                       l4_msgtag(L4_PROTO_LOG, 2 + l4_bytes_to_mwords(size),
00310                                0, L4_MSGTAG_SCHEDULE),
00311                       L4_IPC_NEVER);
00312 }
00313

```

```

00314 L4_INLINE l4_msgtag_t
00315 l4_vcon_send(l4_cap_idx_t vcon, char const *buf, unsigned size) L4_NOTHROW
00316 {
00317     return l4_vcon_send_u(vcon, buf, size, l4_utcb());
00318 }
00319
00320 L4_INLINE long
00321 l4_vcon_write_u(l4_cap_idx_t vcon, char const *buf, unsigned size, l4_utcb_t *utcb) L4_NOTHROW
00322 {
00323     l4_msgtag_t t;
00324
00325     if (size > L4_VCON_WRITE_SIZE)
00326         size = L4_VCON_WRITE_SIZE;
00327
00328     t = l4_vcon_send_u(vcon, buf, size, utcb);
00329     if (l4_msgtag_has_error(t))
00330         return l4_error(t);
00331
00332     return (long) size;
00333 }
00334
00335 L4_INLINE long
00336 l4_vcon_write(l4_cap_idx_t vcon, char const *buf, unsigned size) L4_NOTHROW
00337 {
00338     return l4_vcon_write_u(vcon, buf, size, l4_utcb());
00339 }
00340
00341 L4_INLINE int
00342 l4_vcon_read_with_flags_u(l4_cap_idx_t vcon, char *buf, unsigned size,
00343                          l4_utcb_t *utcb) L4_NOTHROW
00344 {
00345     int ret;
00346     unsigned r;
00347     l4_msg_regs_t *mr;
00348
00349     mr = l4_utcb_mr_u(utcb);
00350     mr->mr[0] = (size << 16) | L4_VCON_READ_OP;
00351
00352     ret = l4_error_u(l4_ipc_call(vcon, utcb,
00353                                l4_msgtag(L4_PROTO_LOG, 1, 0, 0),
00354                                L4_IPC_NEVER),
00355                    utcb);
00356     if (ret < 0)
00357         return ret;
00358
00359     r = mr->mr[0] & L4_VCON_READ_SIZE_MASK;
00360
00361     if (!(mr->mr[0] & L4_VCON_READ_STAT_DONE)) // !eof
00362         ret = size + 1;
00363     else if (r < size)
00364         ret = r;
00365     else
00366         ret = size;
00367
00368     if (L4_LIKELY(buf != NULL))
00369         __builtin_memcpy(buf, &mr->mr[1], r < size ? r : size);
00370
00371     return ret | (mr->mr[0] & ~(L4_VCON_READ_STAT_DONE | L4_VCON_READ_SIZE_MASK));
00372 }
00373
00374 L4_INLINE int
00375 l4_vcon_read_with_flags(l4_cap_idx_t vcon, char *buf, unsigned size) L4_NOTHROW
00376 {
00377     return l4_vcon_read_with_flags_u(vcon, buf, size, l4_utcb());
00378 }
00379
00380 L4_INLINE int
00381 l4_vcon_read_u(l4_cap_idx_t vcon, char *buf, unsigned size, l4_utcb_t *utcb) L4_NOTHROW
00382 {
00383     int r = l4_vcon_read_with_flags_u(vcon, buf, size, utcb);
00384     if (r < 0)
00385         return r;
00386
00387     return r & L4_VCON_READ_SIZE_MASK;
00388 }
00389
00390 L4_INLINE int
00391 l4_vcon_read(l4_cap_idx_t vcon, char *buf, unsigned size) L4_NOTHROW
00392 {
00393     return l4_vcon_read_u(vcon, buf, size, l4_utcb());
00394 }
00395
00396 L4_INLINE l4_msgtag_t
00397 l4_vcon_set_attr_u(l4_cap_idx_t vcon, l4_vcon_attr_t const *attr,
00398                  l4_utcb_t *utcb) L4_NOTHROW
00399 {
00400     l4_msg_regs_t *mr = l4_utcb_mr_u(utcb);

```

```

00401
00402     mr->mr[0] = L4_VCON_SET_ATTR_OP;
00403     __builtin_memcpy(&mr->mr[1], attr, sizeof(*attr));
00404
00405     return l4_ipc_call(vcon, utcb,
00406                       l4_msgtag(L4_PROTO_LOG, 4, 0, 0),
00407                       L4_IPC_NEVER);
00408 }
00409
00410 L4_INLINE l4_msgtag_t
00411 l4_vcon_set_attr(l4_cap_idx_t vcon, l4_vcon_attr_t const *attr) L4_NOTHROW
00412 {
00413     return l4_vcon_set_attr_u(vcon, attr, l4_utcb());
00414 }
00415
00416 L4_INLINE l4_msgtag_t
00417 l4_vcon_get_attr_u(l4_cap_idx_t vcon, l4_vcon_attr_t *attr,
00418                   l4_utcb_t *utcb) L4_NOTHROW
00419 {
00420     l4_msgtag_t res;
00421     l4_msg_regs_t *mr = l4_utcb_mr_u(utcb);
00422
00423     mr->mr[0] = L4_VCON_GET_ATTR_OP;
00424
00425     res = l4_ipc_call(vcon, utcb,
00426                      l4_msgtag(L4_PROTO_LOG, 1, 0, 0),
00427                      L4_IPC_NEVER);
00428     if (l4_error_u(res, utcb) >= 0)
00429         __builtin_memcpy(attr, &mr->mr[1], sizeof(*attr));
00430
00431     return res;
00432 }
00433
00434 L4_INLINE l4_msgtag_t
00435 l4_vcon_get_attr(l4_cap_idx_t vcon, l4_vcon_attr_t *attr) L4_NOTHROW
00436 {
00437     return l4_vcon_get_attr_u(vcon, attr, l4_utcb());
00438 }
00439
00440 L4_INLINE void
00441 l4_vcon_set_attr_raw(l4_vcon_attr_t *attr) L4_NOTHROW
00442 {
00443     attr->i_flags = 0;
00444     attr->o_flags = 0;
00445     attr->l_flags = 0;
00446 }
00447
00448 #ifdef __cplusplus
00449 inline void
00450 l4_vcon_attr_t::set_raw()
00451 { l4_vcon_set_attr_raw(this); }
00452 #endif


```

## 16.612 l4/sys/vcpu\_context File Reference

Hardware vCPU context interface.

```
#include <l4/sys/vcpu_context.h>
```

Include dependency graph for vcpu\_context:



## Namespaces

- namespace [L4](#)  
*L4 low-level kernel interface.*

### 16.612.1 Detailed Description

Hardware vCPU context interface.

Definition in file [vcpu\\_context](#).

### 16.613 vcpu\_context

[Go to the documentation of this file.](#)

```
00001 // vi:set ft=c++: -*- Mode: C++ -*-
00006
00007 #pragma once
00008
00009 #include <l4/sys/vcpu_context.h>
00010
00011 namespace L4 {
00012
00013 class Vcpu_context :
00014     public Kobject_t<Vcpu_context, Kobject, L4_PROTO_VCPU_CONTEXT>
00015 {
00016 public:
00017     Vcpu_context(Vcpu_context const &) = delete;
00018     void operator = (Vcpu_context const &) = delete;
00019
00020 protected:
00021     Vcpu_context();
00022 };
00023
00024 };
```

### 16.614 vcpu\_context.h


```
00001
00006
00007 #pragma once
```

### 16.615 l4/sys/vm File Reference

Virtualization interface.

```
#include <l4/sys/vm.h>
#include <l4/sys/task>
```

Include dependency graph for vm:



## Data Structures

- class [L4::Vm](#)  
*Virtual machine host address space.*

## Namespaces

- namespace [L4](#)  
*[L4](#) low-level kernel interface.*

### 16.615.1 Detailed Description

Virtualization interface.

Definition in file [vm](#).

## 16.616 vm

[Go to the documentation of this file.](#)

```
00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00002 /*
00003  * (c) 2008-2010 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00004  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00005  *      economic rights: Technische Universität Dresden (Germany)
00006  *
00007  * License: see LICENSE.spdx (in this directory or the directories above)
00008  */
00009
00010 #pragma once
00011
00012 #include <l4/sys/vm.h>
00013 #include <l4/sys/task>
00014
00015 namespace L4 {
00016
00017 class Vm : public Kobject_t<Vm, Task, L4_PROTO_VM>
00018 {
00019 public:
00020     #if defined(__arm__) || defined(__aarch64__)
00021         l4_msgtag_t vgicc_map(l4_fpage_t const vgicc_fpage,
00022                               l4_utcb_t *utcb = l4_utcb()) noexcept
00023         { return l4_task_vgicc_map_u(cap(), vgicc_fpage, utcb); }
00024     #endif
00025
00026 protected:
00027     Vm();
00028
00029 private:
00030     Vm(Vm const &);
00031     void operator = (Vm const &);
00032 };
00033
00034 }
```


## 16.617 l4/sys/assert.h File Reference

Low-level assert implementation.


```
#include <l4/sys/compiler.h>
#include <l4/sys/thread.h>
#include <l4/sys/vcon.h>
```



Include dependency graph for assert.h:



This graph shows which files directly or indirectly include this file:



## Macros

- `#define I4_assert(expr)`  
Low-level assert.

## 16.617.1 Detailed Description

Low-level assert implementation.

Definition in file [assert.h](#).

## 16.617.2 Macro Definition Documentation

### 16.617.2.1 l4\_assert

```
#define l4_assert(  
    expr)
```

#### Value:

```
l4_assert_fn(!(expr), __FILE__ ":" L4_stringify(__LINE__) ": Assertion \"" \
    L4_stringify(expr) "\" failed.\n")
```

Low-level assert.

#### Parameters

<i>expr</i>	Expression to be evaluate for the assertion.
-------------	--

This assertion is a low-level implementation that directly uses kernel primitives. Only use `l4_assert()` when the standard `assert()` functionality is not available.

Definition at line 32 of file [assert.h](#).

Referenced by [L4Re::Util::Cap\\_alloc\\_base::free\(\)](#), [L4Re::Util::Counting\\_cap\\_alloc< COUNTERTYPE, Dbg >::free\(\)](#), [L4Re::Util::Counting\\_cap\\_alloc< COUNTERTYPE, Dbg >::release\(\)](#), and [L4Re::Util::Br\\_manager::set\\_rcv\\_cap\\_flags\(\)](#).

## 16.618 assert.h

[Go to the documentation of this file.](#)

```
00001
00005 /*
00006  * (c) 2015 Adam Lackorzynski <adam@l4re.org>
00007  *
00008  * License: see LICENSE.spdx (in this directory or the directories above)
00009  */
00010 #pragma once
00011
00012 #ifdef NDEBUG
00013
00014 #define l4_assert(x) do { } while (0)
00015 #define l4_check(x) do { (void)(x); } while (0)
00016
00017 #else
00018
00019 #include <l4/sys/compiler.h>
00020 #include <l4/sys/thread.h>
00021 #include <l4/sys/vcon.h>
00022
00032 #define l4_assert(expr) \
00033     l4_assert_fn(!(expr), __FILE__ ":" L4_stringify(__LINE__) ": Assertion \"" \
00034         L4_stringify(expr) "\" failed.\n")
00035
00036 #define l4_check(expr) l4_assert(expr)
00037
00041 L4_ALWAYS_INLINE
00042 void l4_assert_fn(unsigned expr, const char *text) L4_NOTHROW;
00043
00047 L4_INLINE L4_NORETURN
00048 void l4_assert_abort(const char *text) L4_NOTHROW;
00049
00050
00051 /* IMPLEMENTATION ----- */
00052
00053 L4_INLINE L4_NORETURN
00054 void l4_assert_abort(const char *text) L4_NOTHROW
00055 {
00056     l4_vcon_write(L4_BASE_LOG_CAP, text, __builtin_strlen(text));
```


```
00057     for (;;)
00058     {
00059         l4_thread_ex_regs(L4_INVALID_CAP, ~0UL, ~0UL,
00060                          L4_THREAD_EX_REGS_TRIGGER_EXCEPTION);
00061     }
00062     L4_ALWAYS_INLINE
00063 void l4_assert_fn(unsigned expr, const char *text) L4_NOTHROW
00064 {
00065     if (L4_LIKELY(expr))
00066         return;
00067     l4_assert_abort(text);
00068 }
00069 #endif /* NDEBUG */
```

## 16.619 l4/util/assert.h File Reference


Some useful assert-style macros.

```
#include <stdio.h>
#include <assert.h>
```

Include dependency graph for assert.h:



This graph shows which files directly or indirectly include this file:



### 16.619.1 Detailed Description

Some useful assert-style macros.

Date

09/2009

Author

Bjoern Doebel [doebel@tudos.org](mailto:doebel@tudos.org)

Definition in file [assert.h](#).

### 16.620 assert.h

[Go to the documentation of this file.](#)

```

00001  /*****
00009  /*
00010  * (c) 2009 Author(s)

```

```

00011  *      economic rights: Technische Universität Dresden (Germany)
00012  * License: see LICENSE.spdx (in this directory or the directories above)
00013  */
00014
00015  /*****
00016  #pragma once
00017
00018  #ifndef NDEBUG
00019
00020  #define DO_NOTHING          do {} while (0)
00021  #define ASSERT_ASSERT(x)    DO_NOTHING
00022  #define ASSERT_VALID(c)     DO_NOTHING
00023  #define ASSERT_EQUAL(a,b)   DO_NOTHING
00024  #define ASSERT_NOT_EQUAL(a,b) DO_NOTHING
00025  #define ASSERT_LOWER_EQ(a,b) DO_NOTHING
00026  #define ASSERT_GREATER_EQ(a,b) DO_NOTHING
00027  #define ASSERT_BETWEEN(a,b,c) DO_NOTHING
00028  #define ASSERT_IPC_OK(i)    DO_NOTHING
00029  #define ASSERT_OK(e)         do { (void)e; } while (0)
00030  #define ASSERT_NOT_NULL(p)   DO_NOTHING
00031  #ifndef assert
00032  #define assert(cond)         DO_NOTHING
00033  #endif
00034
00035  #else // NDEBUG
00036
00037  #ifndef ASSERT_PRINTF
00038  #include <stdio.h>
00039  #define ASSERT_PRINTF printf
00040  #endif
00041  #ifndef ASSERT_ASSERT
00042  #include <assert.h>
00043  #define ASSERT_ASSERT(x) assert(x)
00044  #endif
00045
00046  #define ASSERT_VALID(cap) \
00047      do { \
00048          typeof(cap) _cap = cap; \
00049          if (!l4_is_invalid_cap(_cap)) { \
00050              ASSERT_PRINTF("%s: Cap invalid.\n", __func__); \
00051              ASSERT_ASSERT(!l4_is_invalid_cap(_cap)); \
00052          } \
00053      } while (0)
00054
00055  #define ASSERT_EQUAL(a, b) \
00056      do { \
00057          typeof(a) _a = a; \
00058          typeof(b) _b = b; \
00059          if (_a != _b) { \
00060              ASSERT_PRINTF("%s:\n", __func__); \
00061              ASSERT_PRINTF("    #a" (%lx) != "#b" (%lx)\n", (unsigned long)_a, (unsigned long)_b); \
00062              ASSERT_ASSERT(_a == _b); \
00063          } \
00064      } while (0)
00065
00066  #define ASSERT_NOT_EQUAL(a, b) \
00067      do { \
00068          typeof(a) _a = a; \
00069          typeof(b) _b = b; \
00070          if (_a == _b) { \
00071              ASSERT_PRINTF("%s:\n", __func__); \
00072              ASSERT_PRINTF("    #a" (%lx) == "#b" (%lx)\n", (unsigned long)_a, (unsigned long)_b); \
00073              ASSERT_ASSERT(_a != _b); \
00074          } \
00075      } while (0)
00076
00077  #define ASSERT_LOWER_EQ(val, max) \
00078      do { \
00079          typeof(val) _val = val; \
00080          typeof(max) _max = max; \
00081          if (_val > _max) { \
00082              ASSERT_PRINTF("%s:\n", __func__); \
00083              ASSERT_PRINTF("    #val" (%lx) > "#max" (%lx)\n", (unsigned long)_val, (unsigned long)_max); \
00084              ASSERT_ASSERT(_val <= _max); \
00085          } \
00086      } while (0)
00087
00088  #define ASSERT_GREATER_EQ(val, min) \
00089      do { \
00090          typeof(val) _val = val; \
00091          typeof(min) _min = min; \
00092          if (_val < _min) { \
00093              ASSERT_PRINTF("%s:\n", __func__); \

```

```

00098     ASSERT_PRINTF("    "#val" (%lx) < "#min" (%lx)\n", (unsigned long)_val, (unsigned long)_min); \
00099     ASSERT_ASSERT(_val >= _min); \
00100     } \
00101   } while (0)
00102
00103
00104 #define ASSERT_BETWEEN(val, min, max) \
00105     ASSERT_LOWER_EQ((val), (max)); \
00106     ASSERT_GREATER_EQ((val), (min));
00107
00108
00109 #define ASSERT_IPC_OK(msgtag) \
00110     do { \
00111         int _r = l4_ipc_error(msgtag, l4_utcb()); \
00112         if (_r) { \
00113             ASSERT_PRINTF("%s: IPC Error: %lx\n", __func__, _r); \
00114             ASSERT_ASSERT(_r == 0); \
00115         } \
00116     } while (0)
00117
00118 #define ASSERT_OK(val)          ASSERT_EQUAL((val), 0)
00119 #define ASSERT_NOT_NULL(ptr)    ASSERT_NOT_EQUAL((ptr), (void *)0)
00120
00121 #endif // NDEBUG

```

## 16.621 atomic.h

```


00001
00006 /*
00007  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00008  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00009  *      economic rights: Technische Universität Dresden (Germany)
00010  *
00011  * License: see LICENSE.spdx (in this directory or the directories above)
00012  */
00013 #pragma once
00014
00015 #include <l4/sys/compiler.h>
00016
00017 L4_BEGIN_DECLS
00018
00019 long int
00020 l4_atomic_add(volatile long int* mem, long int offset) L4_NOTHROW L4_LONG_CALL;
00021
00022 long int
00023 l4_atomic_xchg(volatile long int* mem, long int newval) L4_NOTHROW L4_LONG_CALL;
00024
00025 long int
00026 l4_atomic_cmpxchg(volatile long int* mem, long int oldval, long int newval) L4_NOTHROW L4_LONG_CALL;
00027
00028 L4_END_DECLS

```

## 16.622 l4/cxx/atomic.h File Reference

Atomic template.

```
#include <l4/util/atomic.h>
Include dependency graph for atomic.h:
```



## Namespaces

- namespace [L4](#)  
*[L4](#) low-level kernel interface.*

## 16.622.1 Detailed Description

Atomic template.

Definition in file [atomic.h](#).

## 16.623 atomic.h

[Go to the documentation of this file.](#)

```

00001
00005 /*
00006  * (c) 2004-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00007  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00008  *      economic rights: Technische Universität Dresden (Germany)
00009  *
00010  * License: see LICENSE.spdx (in this directory or the directories above)
00011  */
00012 #pragma once
00013
00014 #include <l4/util/atomic.h>
00015
00016 extern "C" void ____error_compare_and_swap_does_not_support_3_bytes____();
00017 extern "C" void ____error_compare_and_swap_does_not_support_more_than_4_bytes____();
00018
00019 namespace L4
```

```

00020 {
00021     template< typename X >
00022     inline int compare_and_swap(X volatile *dst, X old_val, X new_val)
00023     {
00024         switch (sizeof(X))
00025         {
00026             case 1:
00027                 return l4util_cmpxchg8((l4_uint8_t volatile*)dst, old_val, new_val);
00028             case 2:
00029                 return l4util_cmpxchg16((l4_uint16_t volatile *)dst, old_val, new_val);
00030             case 3: ____error_compare_and_swap_does_not_support_3_bytes____();
00031             case 4:
00032                 return l4util_cmpxchg32((l4_uint32_t volatile*)dst, old_val, new_val);
00033             default:
00034                 ____error_compare_and_swap_does_not_support_more_than_4_bytes____();
00035         }
00036         return 0;
00037     }
00038 }

```

## 16.624 I4/util/atomic.h File Reference


atomic operations header and generic implementations

```

#include <l4/sys/l4int.h>
#include <l4/sys/compiler.h>


```

Include dependency graph for atomic.h:





This graph shows which files directly or indirectly include this file:



## Functions

- `int l4util_cmpxchg32` (volatile `l4_uint32_t` \*dest, `l4_uint32_t` cmp\_val, `l4_uint32_t` new\_val)  
*Atomic compare and exchange (32 bit version).*
- `int l4util_cmpxchg16` (volatile `l4_uint16_t` \*dest, `l4_uint16_t` cmp\_val, `l4_uint16_t` new\_val)  
*Atomic compare and exchange (16 bit version).*
- `int l4util_cmpxchg8` (volatile `l4_uint8_t` \*dest, `l4_uint8_t` cmp\_val, `l4_uint8_t` new\_val)  
*Atomic compare and exchange (8 bit version).*
- `int l4util_cmpxchg` (volatile `l4_umword_t` \*dest, `l4_umword_t` cmp\_val, `l4_umword_t` new\_val)  
*Atomic compare and exchange (machine wide fields).*
- `l4_uint32_t l4util_xchg32` (volatile `l4_uint32_t` \*dest, `l4_uint32_t` val)  
*Atomic exchange (32 bit version).*
- `l4_uint16_t l4util_xchg16` (volatile `l4_uint16_t` \*dest, `l4_uint16_t` val)  
*Atomic exchange (16 bit version).*
- `l4_uint8_t l4util_xchg8` (volatile `l4_uint8_t` \*dest, `l4_uint8_t` val)  
*Atomic exchange (8 bit version).*
- `l4_umword_t l4util_xchg` (volatile `l4_umword_t` \*dest, `l4_umword_t` val)  
*Atomic exchange (machine wide fields).*
- `void l4util_atomic_add` (volatile long \*dest, long val)  
*Atomic add.*
- `void l4util_atomic_inc` (volatile long \*dest)  
*Atomic increment.*

## Atomic add/sub/and/or (8,16,32 bit version) without result

- `void l4util_add8` (volatile `l4_uint8_t` \*dest, `l4_uint8_t` val)
- `void l4util_add16` (volatile `l4_uint16_t` \*dest, `l4_uint16_t` val)
- `void l4util_add32` (volatile `l4_uint32_t` \*dest, `l4_uint32_t` val)
- `void l4util_sub8` (volatile `l4_uint8_t` \*dest, `l4_uint8_t` val)
- `void l4util_sub16` (volatile `l4_uint16_t` \*dest, `l4_uint16_t` val)
- `void l4util_sub32` (volatile `l4_uint32_t` \*dest, `l4_uint32_t` val)
- `void l4util_and8` (volatile `l4_uint8_t` \*dest, `l4_uint8_t` val)

- void [l4util\\_and16](#) (volatile [l4\\_uint16\\_t](#) \*dest, [l4\\_uint16\\_t](#) val)
- void [l4util\\_and32](#) (volatile [l4\\_uint32\\_t](#) \*dest, [l4\\_uint32\\_t](#) val)
- void [l4util\\_or8](#) (volatile [l4\\_uint8\\_t](#) \*dest, [l4\\_uint8\\_t](#) val)
- void [l4util\\_or16](#) (volatile [l4\\_uint16\\_t](#) \*dest, [l4\\_uint16\\_t](#) val)
- void [l4util\\_or32](#) (volatile [l4\\_uint32\\_t](#) \*dest, [l4\\_uint32\\_t](#) val)

#### Atomic add/sub/and/or operations (8,16,32 bit) with result

- [l4\\_uint8\\_t l4util\\_add8\\_res](#) (volatile [l4\\_uint8\\_t](#) \*dest, [l4\\_uint8\\_t](#) val)
- [l4\\_uint16\\_t l4util\\_add16\\_res](#) (volatile [l4\\_uint16\\_t](#) \*dest, [l4\\_uint16\\_t](#) val)
- [l4\\_uint32\\_t l4util\\_add32\\_res](#) (volatile [l4\\_uint32\\_t](#) \*dest, [l4\\_uint32\\_t](#) val)
- [l4\\_uint8\\_t l4util\\_sub8\\_res](#) (volatile [l4\\_uint8\\_t](#) \*dest, [l4\\_uint8\\_t](#) val)
- [l4\\_uint16\\_t l4util\\_sub16\\_res](#) (volatile [l4\\_uint16\\_t](#) \*dest, [l4\\_uint16\\_t](#) val)
- [l4\\_uint32\\_t l4util\\_sub32\\_res](#) (volatile [l4\\_uint32\\_t](#) \*dest, [l4\\_uint32\\_t](#) val)
- [l4\\_uint8\\_t l4util\\_and8\\_res](#) (volatile [l4\\_uint8\\_t](#) \*dest, [l4\\_uint8\\_t](#) val)
- [l4\\_uint16\\_t l4util\\_and16\\_res](#) (volatile [l4\\_uint16\\_t](#) \*dest, [l4\\_uint16\\_t](#) val)
- [l4\\_uint32\\_t l4util\\_and32\\_res](#) (volatile [l4\\_uint32\\_t](#) \*dest, [l4\\_uint32\\_t](#) val)
- [l4\\_uint8\\_t l4util\\_or8\\_res](#) (volatile [l4\\_uint8\\_t](#) \*dest, [l4\\_uint8\\_t](#) val)
- [l4\\_uint16\\_t l4util\\_or16\\_res](#) (volatile [l4\\_uint16\\_t](#) \*dest, [l4\\_uint16\\_t](#) val)
- [l4\\_uint32\\_t l4util\\_or32\\_res](#) (volatile [l4\\_uint32\\_t](#) \*dest, [l4\\_uint32\\_t](#) val)

#### Atomic inc/dec (8,16,32 bit) without result

- void [l4util\\_inc8](#) (volatile [l4\\_uint8\\_t](#) \*dest)
- void [l4util\\_inc16](#) (volatile [l4\\_uint16\\_t](#) \*dest)
- void [l4util\\_inc32](#) (volatile [l4\\_uint32\\_t](#) \*dest)
- void [l4util\\_dec8](#) (volatile [l4\\_uint8\\_t](#) \*dest)
- void [l4util\\_dec16](#) (volatile [l4\\_uint16\\_t](#) \*dest)
- void [l4util\\_dec32](#) (volatile [l4\\_uint32\\_t](#) \*dest)

#### Atomic inc/dec (8,16,32 bit) with result

- [l4\\_uint8\\_t l4util\\_inc8\\_res](#) (volatile [l4\\_uint8\\_t](#) \*dest)
- [l4\\_uint16\\_t l4util\\_inc16\\_res](#) (volatile [l4\\_uint16\\_t](#) \*dest)
- [l4\\_uint32\\_t l4util\\_inc32\\_res](#) (volatile [l4\\_uint32\\_t](#) \*dest)
- [l4\\_uint8\\_t l4util\\_dec8\\_res](#) (volatile [l4\\_uint8\\_t](#) \*dest)
- [l4\\_uint16\\_t l4util\\_dec16\\_res](#) (volatile [l4\\_uint16\\_t](#) \*dest)
- [l4\\_uint32\\_t l4util\\_dec32\\_res](#) (volatile [l4\\_uint32\\_t](#) \*dest)

## 16.624.1 Detailed Description

atomic operations header and generic implementations

Date

10/20/2000

Author

Lars Reuther [reuther@os.inf.tu-dresden.de](mailto:reuther@os.inf.tu-dresden.de), Jork Loeser [jork@os.inf.tu-dresden.de](mailto:jork@os.inf.tu-dresden.de)

Definition in file [atomic.h](#).

## 16.625 atomic.h

[Go to the documentation of this file.](#)

```

00001 /*****
00010 */
00011 * (c) 2000-2009 Author(s)
00012 *     economic rights: Technische Universität Dresden (Germany)
00013 * License: see LICENSE.spdx (in this directory or the directories above)
00014 */
00015
00016 /*****
00017 #ifndef __L4UTIL__INCLUDE__ATOMIC_H__
00018 #define __L4UTIL__INCLUDE__ATOMIC_H__
00019
00020 #include <l4/sys/l4int.h>
00021 #include <l4/sys/compiler.h>
00022
00023 /*****
00024 *** Prototypes
00025 *****/
00026
00027 L4_BEGIN_DECLS
00028
00029
00030
00031 #if __SIZEOF_LONG__ == 8
00032
00033
00034 L4_INLINE int
00035 l4util_cmpxchg64(volatile l4_uint64_t * dest,
00036                 l4_uint64_t cmp_val, l4_uint64_t new_val);
00037
00038 #endif
00039
00040 L4_INLINE int
00041 l4util_cmpxchg32(volatile l4_uint32_t * dest,
00042                 l4_uint32_t cmp_val, l4_uint32_t new_val);
00043
00044 L4_INLINE int
00045 l4util_cmpxchg16(volatile l4_uint16_t * dest,
00046                 l4_uint16_t cmp_val, l4_uint16_t new_val);
00047
00048 L4_INLINE int
00049 l4util_cmpxchg8(volatile l4_uint8_t * dest,
00050                l4_uint8_t cmp_val, l4_uint8_t new_val);
00051
00052 L4_INLINE int
00053 l4util_cmpxchg(volatile l4_umword_t * dest,
00054                l4_umword_t cmp_val, l4_umword_t new_val);
00055
00056 L4_INLINE l4_uint32_t
00057 l4util_xchg32(volatile l4_uint32_t * dest, l4_uint32_t val);
00058
00059 L4_INLINE l4_uint16_t
00060 l4util_xchg16(volatile l4_uint16_t * dest, l4_uint16_t val);
00061
00062 L4_INLINE l4_uint8_t
00063 l4util_xchg8(volatile l4_uint8_t * dest, l4_uint8_t val);
00064
00065 L4_INLINE l4_umword_t
00066 l4util_xchg(volatile l4_umword_t * dest, l4_umword_t val);
00067
00068
00069 L4_INLINE void
00070 l4util_add8(volatile l4_uint8_t *dest, l4_uint8_t val);
00071 L4_INLINE void
00072 l4util_add16(volatile l4_uint16_t *dest, l4_uint16_t val);
00073 L4_INLINE void
00074 l4util_add32(volatile l4_uint32_t *dest, l4_uint32_t val);
00075 L4_INLINE void
00076 l4util_sub8(volatile l4_uint8_t *dest, l4_uint8_t val);
00077 L4_INLINE void
00078 l4util_sub16(volatile l4_uint16_t *dest, l4_uint16_t val);
00079 L4_INLINE void
00080 l4util_sub32(volatile l4_uint32_t *dest, l4_uint32_t val);
00081 L4_INLINE void
00082 l4util_and8(volatile l4_uint8_t *dest, l4_uint8_t val);
00083 L4_INLINE void
00084 l4util_and16(volatile l4_uint16_t *dest, l4_uint16_t val);
00085 L4_INLINE void
00086 l4util_and32(volatile l4_uint32_t *dest, l4_uint32_t val);
00087 L4_INLINE void
00088 l4util_or8(volatile l4_uint8_t *dest, l4_uint8_t val);
00089 L4_INLINE void
00090 l4util_or16(volatile l4_uint16_t *dest, l4_uint16_t val);
00091 L4_INLINE void
00092 l4util_or32(volatile l4_uint32_t *dest, l4_uint32_t val);

```

```

00220
00222
00229 L4_INLINE l4_uint8_t
00230 l4util_add8_res(volatile l4_uint8_t *dest, l4_uint8_t val);
00232 L4_INLINE l4_uint16_t
00233 l4util_add16_res(volatile l4_uint16_t *dest, l4_uint16_t val);
00235 L4_INLINE l4_uint32_t
00236 l4util_add32_res(volatile l4_uint32_t *dest, l4_uint32_t val);
00238 L4_INLINE l4_uint8_t
00239 l4util_sub8_res(volatile l4_uint8_t *dest, l4_uint8_t val);
00241 L4_INLINE l4_uint16_t
00242 l4util_sub16_res(volatile l4_uint16_t *dest, l4_uint16_t val);
00244 L4_INLINE l4_uint32_t
00245 l4util_sub32_res(volatile l4_uint32_t *dest, l4_uint32_t val);
00247 L4_INLINE l4_uint8_t
00248 l4util_and8_res(volatile l4_uint8_t *dest, l4_uint8_t val);
00250 L4_INLINE l4_uint16_t
00251 l4util_and16_res(volatile l4_uint16_t *dest, l4_uint16_t val);
00253 L4_INLINE l4_uint32_t
00254 l4util_and32_res(volatile l4_uint32_t *dest, l4_uint32_t val);
00256 L4_INLINE l4_uint8_t
00257 l4util_or8_res(volatile l4_uint8_t *dest, l4_uint8_t val);
00259 L4_INLINE l4_uint16_t
00260 l4util_or16_res(volatile l4_uint16_t *dest, l4_uint16_t val);
00262 L4_INLINE l4_uint32_t
00263 l4util_or32_res(volatile l4_uint32_t *dest, l4_uint32_t val);
00265
00267
00272 L4_INLINE void
00273 l4util_inc8(volatile l4_uint8_t *dest);
00275 L4_INLINE void
00276 l4util_inc16(volatile l4_uint16_t *dest);
00278 L4_INLINE void
00279 l4util_inc32(volatile l4_uint32_t *dest);
00281 L4_INLINE void
00282 l4util_dec8(volatile l4_uint8_t *dest);
00284 L4_INLINE void
00285 l4util_dec16(volatile l4_uint16_t *dest);
00287 L4_INLINE void
00288 l4util_dec32(volatile l4_uint32_t *dest);
00290
00292
00298 L4_INLINE l4_uint8_t
00299 l4util_inc8_res(volatile l4_uint8_t *dest);
00301 L4_INLINE l4_uint16_t
00302 l4util_inc16_res(volatile l4_uint16_t *dest);
00304 L4_INLINE l4_uint32_t
00305 l4util_inc32_res(volatile l4_uint32_t *dest);
00307 L4_INLINE l4_uint8_t
00308 l4util_dec8_res(volatile l4_uint8_t *dest);
00310 L4_INLINE l4_uint16_t
00311 l4util_dec16_res(volatile l4_uint16_t *dest);
00313 L4_INLINE l4_uint32_t
00314 l4util_dec32_res(volatile l4_uint32_t *dest);
00316
00324 L4_INLINE void
00325 l4util_atomic_add(volatile long *dest, long val);
00326
00333 L4_INLINE void
00334 l4util_atomic_inc(volatile long *dest);
00335
00336 L4_END_DECLS
00337
00338 /*****
00339  * IMPLEMENTATION *
00340  *****/
00341
00342 #if __SIZEOF_LONG__ == 8
00343
00344 L4_INLINE int
00345 l4util_cmpxchg64(volatile l4_uint64_t * dest,
00346                  l4_uint64_t cmp_val, l4_uint64_t new_val)
00347 {
00348     return __atomic_compare_exchange_n(dest, &cmp_val, new_val, 0,
00349                                         __ATOMIC_SEQ_CST, __ATOMIC_SEQ_CST);
00350 }
00351
00352 #endif
00353
00354 L4_INLINE int
00355 l4util_cmpxchg32(volatile l4_uint32_t * dest,
00356                  l4_uint32_t cmp_val, l4_uint32_t new_val)
00357 {
00358     return __atomic_compare_exchange_n(dest, &cmp_val, new_val, 0,
00359                                         __ATOMIC_SEQ_CST, __ATOMIC_SEQ_CST);
00360 }
00361

```

```

00362 L4_INLINE int
00363 l4util_cmpxchg16(volatile l4_uint16_t * dest,
00364                  l4_uint16_t cmp_val, l4_uint16_t new_val)
00365 {
00366     return __atomic_compare_exchange_n(dest, &cmp_val, new_val, 0,
00367                                         __ATOMIC_SEQ_CST, __ATOMIC_SEQ_CST);
00368 }
00369
00370 L4_INLINE int
00371 l4util_cmpxchg8(volatile l4_uint8_t * dest,
00372                 l4_uint8_t cmp_val, l4_uint8_t new_val)
00373 {
00374     return __atomic_compare_exchange_n(dest, &cmp_val, new_val, 0,
00375                                         __ATOMIC_SEQ_CST, __ATOMIC_SEQ_CST);
00376 }
00377
00378 L4_INLINE int
00379 l4util_cmpxchg(volatile l4_umword_t * dest,
00380                l4_umword_t cmp_val, l4_umword_t new_val)
00381 {
00382     return __atomic_compare_exchange_n(dest, &cmp_val, new_val, 0,
00383                                         __ATOMIC_SEQ_CST, __ATOMIC_SEQ_CST);
00384 }
00385
00386 L4_INLINE l4_uint32_t
00387 l4util_xchg32(volatile l4_uint32_t * dest, l4_uint32_t val)
00388 {
00389     return __atomic_exchange_n(dest, val, __ATOMIC_SEQ_CST);
00390 }
00391
00392 L4_INLINE l4_uint16_t
00393 l4util_xchg16(volatile l4_uint16_t * dest, l4_uint16_t val)
00394 {
00395     return __atomic_exchange_n(dest, val, __ATOMIC_SEQ_CST);
00396 }
00397
00398 L4_INLINE l4_uint8_t
00399 l4util_xchg8(volatile l4_uint8_t * dest, l4_uint8_t val)
00400 {
00401     return __atomic_exchange_n(dest, val, __ATOMIC_SEQ_CST);
00402 }
00403
00404 L4_INLINE l4_umword_t
00405 l4util_xchg(volatile l4_umword_t * dest, l4_umword_t val)
00406 {
00407     return __atomic_exchange_n(dest, val, __ATOMIC_SEQ_CST);
00408 }
00409
00410 L4_INLINE void
00411 l4util_inc8(volatile l4_uint8_t *dest)
00412 { __atomic_fetch_add(dest, 1, __ATOMIC_SEQ_CST); }
00413
00414 L4_INLINE void
00415 l4util_inc16(volatile l4_uint16_t *dest)
00416 { __atomic_fetch_add(dest, 1, __ATOMIC_SEQ_CST); }
00417
00418 L4_INLINE void
00419 l4util_inc32(volatile l4_uint32_t *dest)
00420 { __atomic_fetch_add(dest, 1, __ATOMIC_SEQ_CST); }
00421
00422 L4_INLINE void
00423 l4util_atomic_inc(volatile long *dest)
00424 { __atomic_fetch_add(dest, 1, __ATOMIC_SEQ_CST); }
00425
00426 L4_INLINE void
00427 l4util_dec8(volatile l4_uint8_t *dest)
00428 { __atomic_fetch_sub(dest, 1, __ATOMIC_SEQ_CST); }
00429
00430 L4_INLINE void
00431 l4util_dec16(volatile l4_uint16_t *dest)
00432 { __atomic_fetch_sub(dest, 1, __ATOMIC_SEQ_CST); }
00433
00434 L4_INLINE void
00435 l4util_dec32(volatile l4_uint32_t *dest)
00436 { __atomic_fetch_sub(dest, 1, __ATOMIC_SEQ_CST); }
00437
00438
00439 L4_INLINE l4_uint8_t
00440 l4util_inc8_res(volatile l4_uint8_t *dest)
00441 { return __atomic_add_fetch(dest, 1, __ATOMIC_SEQ_CST); }
00442
00443 L4_INLINE l4_uint16_t
00444 l4util_inc16_res(volatile l4_uint16_t *dest)
00445 { return __atomic_add_fetch(dest, 1, __ATOMIC_SEQ_CST); }
00446
00447 L4_INLINE l4_uint32_t
00448 l4util_inc32_res(volatile l4_uint32_t *dest)

```

```

00449 { return __atomic_add_fetch(dest, 1, __ATOMIC_SEQ_CST); }
00450
00451 L4_INLINE l4_uint8_t
00452 l4util_dec8_res(volatile l4_uint8_t *dest)
00453 { return __atomic_sub_fetch(dest, 1, __ATOMIC_SEQ_CST); }
00454
00455 L4_INLINE l4_uint16_t
00456 l4util_dec16_res(volatile l4_uint16_t *dest)
00457 { return __atomic_sub_fetch(dest, 1, __ATOMIC_SEQ_CST); }
00458
00459 L4_INLINE l4_uint32_t
00460 l4util_dec32_res(volatile l4_uint32_t *dest)
00461 { return __atomic_sub_fetch(dest, 1, __ATOMIC_SEQ_CST); }
00462
00463 L4_INLINE l4_umword_t
00464 l4util_dec_res(volatile l4_umword_t *dest)
00465 { return __atomic_sub_fetch(dest, 1, __ATOMIC_SEQ_CST); }
00466
00467 L4_INLINE void
00468 l4util_add8(volatile l4_uint8_t *dest, l4_uint8_t val)
00469 { __atomic_fetch_add(dest, val, __ATOMIC_SEQ_CST); }
00470
00471 L4_INLINE void
00472 l4util_add16(volatile l4_uint16_t *dest, l4_uint16_t val)
00473 { __atomic_fetch_add(dest, val, __ATOMIC_SEQ_CST); }
00474
00475 L4_INLINE void
00476 l4util_add32(volatile l4_uint32_t *dest, l4_uint32_t val)
00477 { __atomic_fetch_add(dest, val, __ATOMIC_SEQ_CST); }
00478
00479 L4_INLINE void
00480 l4util_atomic_add(volatile long *dest, long val)
00481 { __atomic_fetch_add(dest, val, __ATOMIC_SEQ_CST); }
00482
00483 L4_INLINE void
00484 l4util_sub8(volatile l4_uint8_t *dest, l4_uint8_t val)
00485 { __atomic_fetch_sub(dest, val, __ATOMIC_SEQ_CST); }
00486
00487 L4_INLINE void
00488 l4util_sub16(volatile l4_uint16_t *dest, l4_uint16_t val)
00489 { __atomic_fetch_sub(dest, val, __ATOMIC_SEQ_CST); }
00490
00491 L4_INLINE void
00492 l4util_sub32(volatile l4_uint32_t *dest, l4_uint32_t val)
00493 { __atomic_fetch_sub(dest, val, __ATOMIC_SEQ_CST); }
00494
00495 L4_INLINE void
00496 l4util_and8(volatile l4_uint8_t *dest, l4_uint8_t val)
00497 { __atomic_fetch_and(dest, val, __ATOMIC_SEQ_CST); }
00498
00499 L4_INLINE void
00500 l4util_and16(volatile l4_uint16_t *dest, l4_uint16_t val)
00501 { __atomic_fetch_and(dest, val, __ATOMIC_SEQ_CST); }
00502
00503 L4_INLINE void
00504 l4util_and32(volatile l4_uint32_t *dest, l4_uint32_t val)
00505 { __atomic_fetch_and(dest, val, __ATOMIC_SEQ_CST); }
00506
00507 L4_INLINE void
00508 l4util_or8(volatile l4_uint8_t *dest, l4_uint8_t val)
00509 { __atomic_fetch_or(dest, val, __ATOMIC_SEQ_CST); }
00510
00511 L4_INLINE void
00512 l4util_or16(volatile l4_uint16_t *dest, l4_uint16_t val)
00513 { __atomic_fetch_or(dest, val, __ATOMIC_SEQ_CST); }
00514
00515 L4_INLINE void
00516 l4util_or32(volatile l4_uint32_t *dest, l4_uint32_t val)
00517 { __atomic_fetch_or(dest, val, __ATOMIC_SEQ_CST); }
00518
00519 L4_INLINE l4_uint8_t
00520 l4util_add8_res(volatile l4_uint8_t *dest, l4_uint8_t val)
00521 { return __atomic_add_fetch(dest, val, __ATOMIC_SEQ_CST); }
00522
00523 L4_INLINE l4_uint16_t
00524 l4util_add16_res(volatile l4_uint16_t *dest, l4_uint16_t val)
00525 { return __atomic_add_fetch(dest, val, __ATOMIC_SEQ_CST); }
00526
00527 L4_INLINE l4_uint32_t
00528 l4util_add32_res(volatile l4_uint32_t *dest, l4_uint32_t val)
00529 { return __atomic_add_fetch(dest, val, __ATOMIC_SEQ_CST); }
00530
00531 L4_INLINE l4_uint8_t
00532 l4util_sub8_res(volatile l4_uint8_t *dest, l4_uint8_t val)
00533 { return __atomic_sub_fetch(dest, val, __ATOMIC_SEQ_CST); }
00534
00535 L4_INLINE l4_uint16_t

```

```


00536 l4util_sub16_res(volatile l4_uint16_t *dest, l4_uint16_t val)
00537 { return __atomic_sub_fetch(dest, val, __ATOMIC_SEQ_CST); }
00538
00539 L4_INLINE l4_uint32_t
00540 l4util_sub32_res(volatile l4_uint32_t *dest, l4_uint32_t val)
00541 { return __atomic_sub_fetch(dest, val, __ATOMIC_SEQ_CST); }
00542
00543 L4_INLINE l4_uint8_t
00544 l4util_and8_res(volatile l4_uint8_t *dest, l4_uint8_t val)
00545 { return __atomic_and_fetch(dest, val, __ATOMIC_SEQ_CST); }
00546
00547 L4_INLINE l4_uint16_t
00548 l4util_and16_res(volatile l4_uint16_t *dest, l4_uint16_t val)
00549 { return __atomic_and_fetch(dest, val, __ATOMIC_SEQ_CST); }
00550
00551 L4_INLINE l4_uint32_t
00552 l4util_and32_res(volatile l4_uint32_t *dest, l4_uint32_t val)
00553 { return __atomic_and_fetch(dest, val, __ATOMIC_SEQ_CST); }
00554
00555 L4_INLINE l4_uint8_t
00556 l4util_or8_res(volatile l4_uint8_t *dest, l4_uint8_t val)
00557 { return __atomic_or_fetch(dest, val, __ATOMIC_SEQ_CST); }
00558
00559 L4_INLINE l4_uint16_t
00560 l4util_or16_res(volatile l4_uint16_t *dest, l4_uint16_t val)
00561 { return __atomic_or_fetch(dest, val, __ATOMIC_SEQ_CST); }
00562
00563 L4_INLINE l4_uint32_t
00564 l4util_or32_res(volatile l4_uint32_t *dest, l4_uint32_t val)
00565 { return __atomic_or_fetch(dest, val, __ATOMIC_SEQ_CST); }
00566
00567 #endif /* ! __L4UTIL__INCLUDE__ATOMIC_H__ */

```


## 16.626 l4/util/backtrace.h File Reference

Backtrace.

#include <l4/sys/compiler.h>  
 Include dependency graph for backtrace.h:



This graph shows which files directly or indirectly include this file:



Functions

- `L4_BEGIN_DECLS` `int l4util_backtrace` (`void **pc_array`, `int max_len`)  
*Fill backtrace structure.*

16.626.1 Detailed Description

Backtrace.

Definition in file [backtrace.h](#).

16.626.2 Function Documentation

16.626.2.1 `l4util_backtrace()`

```
L4_BEGIN_DECLS
int l4util_backtrace (
    void ** pc_array,
    int max_len)

```

Fill backtrace structure.

Parameters

<code>pc_array</code>	Array of instruction pointers.
<code>max_len</code>	Length of array.




### Returns

Number of entries

References [L4\\_END\\_DECLS](#).

Referenced by [L4::Exception\\_tracer::Exception\\_tracer\(\)](#).

Here is the caller graph for this function:



## 16.627 backtrace.h

[Go to the documentation of this file.](#)


```
00001
00005 /*
00006  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00007  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00008  *      economic rights: Technische Universität Dresden (Germany)
00009  * License: see LICENSE.spdx (in this directory or the directories above)
00010  */
00011 #pragma once
00012
00013 #include <l4/sys/compiler.h>
00014
00015 L4\_BEGIN\_DECLS
00016
00024 int l4util_backtrace(void **pc_array, int max_len);
00025
00026 L4\_END\_DECLS
```

## 16.628 l4/util/base64.h File Reference

base 64 encoding and decoding functions adapted from Bob Trower 08/04/01

```
#include <l4/sys/compiler.h>
```

Include dependency graph for base64.h:



## Functions

- void **base64\_encode** (const char \*infile, unsigned int in\_size, char \*\*outfile)  
*base-64-encode string infile*
- void **base64\_decode** (const char \*infile, unsigned int in\_size, char \*\*outfile)  
*decode base-64-encoded string infile*

### 16.628.1 Detailed Description

base 64 encoding and decoding functions adapted from Bob Trower 08/04/01

#### Date

04/26/2002

#### Author

Joerg Nothnagel [jn6@os.inf.tu-dresden.de](mailto:jn6@os.inf.tu-dresden.de)

Definition in file [base64.h](#).

## 16.629 base64.h

[Go to the documentation of this file.](#)

```

00001
00009 /*
00010  * (c) 2008-2009 Author(s)
00011  *     economic rights: Technische Universität Dresden (Germany)
00012  * License: see LICENSE.spdx (in this directory or the directories above)
00013  */
00014
00015 #ifndef B64_EN_DECODE
00016 #define B64_EN_DECODE
00017
00018 #include <l4/sys/compiler.h>
00019
00020 L4_BEGIN_DECLS
00021
00027
00038 L4_CV void base64_encode( const char *infile, unsigned int in_size, char **outfile);
00039
00050 L4_CV void base64_decode(const char *infile, unsigned int in_size, char **outfile);
00051
00052 L4_END_DECLS
00053
00055 #endif //B64_EN_DECODE

```

## 16.630 l4/util/bitops.h File Reference


bit manipulation functions

```


#include <l4/sys/l4int.h>
#include <l4/sys/compiler.h>
#include <l4/util/bitops_arch.h>
#include <l4/util/atomic.h>

```

Include dependency graph for bitops.h:



This graph shows which files directly or indirectly include this file:



## Macros

- `#define l4util_test_and_clear_bit(b, dest)`  
*define some more usual names*

## Functions

- `void l4util_set_bit (int b, volatile l4_umword_t *dest)`  
*Set bit in memory.*
- `void l4util_clear_bit (int b, volatile l4_umword_t *dest)`  
*Clear bit in memory.*
- `void l4util_complement_bit (int b, volatile l4_umword_t *dest)`  
*Complement bit in memory.*
- `int l4util_test_bit (int b, const volatile l4_umword_t *dest)`  
*Test bit (return value of bit).*
- `int l4util_bts (int b, volatile l4_umword_t *dest)`  
*Bit test and set.*
- `int l4util_btr (int b, volatile l4_umword_t *dest)`  
*Bit test and reset.*
- `int l4util_btc (int b, volatile l4_umword_t *dest)`  
*Bit test and complement.*
- `int l4util_bsr (l4_umword_t word)`  
*Bit scan reverse.*
- `int l4util_bsf (l4_umword_t word)`  
*Bit scan forward.*
- `int l4util_find_first_set_bit (const void *dest, l4_size_t size)`  
*Find the first set bit in a memory region.*
- `int l4util_find_first_zero_bit (const void *dest, l4_size_t size)`  
*Find the first zero bit in a memory region.*
- `int l4util_next_power2 (unsigned long val)`  
*Find the next power of 2 for a given number.*

## 16.630.1 Detailed Description

bit manipulation functions

### Date

07/03/2001

### Author

Lars Reuther [reuther@os.inf.tu-dresden.de](mailto:reuther@os.inf.tu-dresden.de)

Definition in file [bitops.h](#).

## 16.631 bitops.h

[Go to the documentation of this file.](#)

```

00001  /*****
00009  */
00010  * (c) 2000-2009 Author(s)
00011  *     economic rights: Technische Universität Dresden (Germany)
00012  * License: see LICENSE.spdx (in this directory or the directories above)
00013  */
00014
00015  /*****
00016  #ifndef __L4UTIL__INCLUDE__BITOPS_H__
00017  #define __L4UTIL__INCLUDE__BITOPS_H__
00018
00019  /* L4 includes */
00020  #include <l4/sys/l4int.h>
00021  #include <l4/sys/compiler.h>
00022
00024  #define l4util_test_and_clear_bit(b, dest)  l4util_btr(b, dest)
00025  #define l4util_test_and_set_bit(b, dest)    l4util_bts(b, dest)
00026  #define l4util_test_and_change_bit(b, dest) l4util_btc(b, dest)
00027  #define l4util_log2(word)                  l4util_bsr(word)
00028
00029  /*****
00030  *** Prototypes
00031  *****/
00032
00033  L4_BEGIN_DECLS
00034
00039
00047  L4_INLINE void
00048  l4util_set_bit(int b, volatile l4_umword_t * dest);
00049
00057  L4_INLINE void
00058  l4util_clear_bit(int b, volatile l4_umword_t * dest);
00059
00067  L4_INLINE void
00068  l4util_complement_bit(int b, volatile l4_umword_t * dest);
00069
00079  L4_INLINE int
00080  l4util_test_bit(int b, const volatile l4_umword_t * dest);
00081
00093  L4_INLINE int
00094  l4util_bts(int b, volatile l4_umword_t * dest);
00095
00107  L4_INLINE int
00108  l4util_btr(int b, volatile l4_umword_t * dest);
00109
00121  L4_INLINE int
00122  l4util_btc(int b, volatile l4_umword_t * dest);
00123
00135  L4_INLINE int
00136  l4util_bsr(l4_umword_t word);
00137
00149  L4_INLINE int
00150  l4util_bsf(l4_umword_t word);
00151
00163  L4_INLINE int

```

```

00164 l4util_find_first_set_bit(const void * dest, l4_size_t size);
00165
00177 L4_INLINE int
00178 l4util_find_first_zero_bit(const void * dest, l4_size_t size);
00179
00180
00189 L4_INLINE int
00190 l4util_next_power2(unsigned long val);
00191
00192 L4_END_DECLS
00193
00194 /*****
00195  *** Implementation of specific version
00196  *****/
00197
00198 #include <l4/util/bitops_arch.h>
00199
00200 /*****
00201  *** Generic implementations
00202  *****/
00203
00204 #ifndef __L4UTIL_BITOPS_HAVE_ARCH_SET_BIT
00205 #include <l4/util/atomic.h>
00206 L4_INLINE void
00207 l4util_set_bit(int b, volatile l4_umword_t * dest)
00208 {
00209     l4_umword_t oldval, newval;
00210
00211     dest += b / (sizeof(*dest) * 8); /* advance dest to the proper element */
00212     b    &= sizeof(*dest) * 8 - 1; /* modulo; cut off all upper bits */
00213
00214     do
00215     {
00216         oldval = *dest;
00217         newval = oldval | (1UL << b);
00218     }
00219     while (!l4util_cmpxchg(dest, oldval, newval));
00220 }
00221 #endif
00222
00223 #ifndef __L4UTIL_BITOPS_HAVE_ARCH_CLEAR_BIT
00224 #include <l4/util/atomic.h>
00225 L4_INLINE void
00226 l4util_clear_bit(int b, volatile l4_umword_t * dest)
00227 {
00228     l4_umword_t oldval, newval;
00229
00230     dest += b / (sizeof(*dest) * 8);
00231     b    &= sizeof(*dest) * 8 - 1;
00232
00233     do
00234     {
00235         oldval = *dest;
00236         newval = oldval & ~(1UL << b);
00237     }
00238     while (!l4util_cmpxchg(dest, oldval, newval));
00239 }
00240 #endif
00241
00242 #ifndef __L4UTIL_BITOPS_HAVE_ARCH_TEST_BIT
00243 L4_INLINE int
00244 l4util_test_bit(int b, const volatile l4_umword_t * dest)
00245 {
00246     dest += b / (sizeof(*dest) * 8);
00247     b    &= sizeof(*dest) * 8 - 1;
00248
00249     return (*dest >> b) & 1;
00250 }
00251 #endif
00252
00253 #ifndef __L4UTIL_BITOPS_HAVE_ARCH_BIT_TEST_AND_SET
00254 #include <l4/util/atomic.h>
00255 L4_INLINE int
00256 l4util_bts(int b, volatile l4_umword_t * dest)
00257 {
00258     l4_umword_t oldval, newval;
00259
00260     dest += b / (sizeof(*dest) * 8);
00261     b    &= sizeof(*dest) * 8 - 1;
00262
00263     do
00264     {
00265         oldval = *dest;
00266         newval = oldval | (1UL << b);
00267     }
00268     while (!l4util_cmpxchg(dest, oldval, newval));
00269

```

```

00270  /* Return old bit */
00271  return (oldval >> b) & 1;
00272 }
00273 #endif
00274
00275 #ifndef __L4UTIL_BITOPS_HAVE_ARCH_BIT_TEST_AND_RESET
00276 #include <l4/util/atomic.h>
00277 L4_INLINE int
00278 l4util_btr(int b, volatile l4_umword_t * dest)
00279 {
00280     l4_umword_t oldval, newval;
00281
00282     dest += b / (sizeof(*dest) * 8);
00283     b    &= sizeof(*dest) * 8 - 1;
00284
00285     do
00286     {
00287         oldval = *dest;
00288         newval = oldval & ~(1UL << b);
00289     }
00290     while (!l4util_cmpxchg(dest, oldval, newval));
00291
00292     /* Return old bit */
00293     return (oldval >> b) & 1;
00294 }
00295 #endif
00296
00297 #ifndef __L4UTIL_BITOPS_HAVE_ARCH_BIT_SCAN_REVERSE
00298 L4_INLINE int
00299 l4util_bsr(l4_umword_t word)
00300 {
00301     int i;
00302
00303     if (!word)
00304         return -1;
00305
00306     for (i = 8 * sizeof(word) - 1; i >= 0; i--)
00307         if ((1UL << i) & word)
00308             return i;
00309
00310     __builtin_unreachable();
00311 }
00312 #endif
00313
00314 #ifndef __L4UTIL_BITOPS_HAVE_ARCH_BIT_SCAN_FORWARD
00315 L4_INLINE int
00316 l4util_bsf(l4_umword_t word)
00317 {
00318     unsigned int i;
00319
00320     if (!word)
00321         return -1;
00322
00323     for (i = 0; i < sizeof(word) * 8; i++)
00324         if ((1UL << i) & word)
00325             return i;
00326
00327     __builtin_unreachable();
00328 }
00329 #endif
00330
00331 #ifndef __L4UTIL_BITOPS_HAVE_ARCH_FIND_FIRST_ZERO_BIT
00332 L4_INLINE int
00333 l4util_find_first_zero_bit(const void * dest, l4_size_t size)
00334 {
00335     l4_size_t i, j;
00336     unsigned long *v = (unsigned long*)dest;
00337
00338     if (!size)
00339         return 0;
00340
00341     size = (size + 31) & ~0x1f; /* Grmbl: adapt to x86 implementation... */
00342
00343     for (i = j = 0; i < size; i++, j++)
00344     {
00345         if (j >= sizeof(*v) * 8)
00346         {
00347             j = 0;
00348             v++;
00349         }
00350         if (!((1UL << j) & *v))
00351             return i;
00352     }
00353     return size + 1;
00354 }
00355 #endif
00356

```

```

00357 #ifndef __L4UTIL_BITOPS_HAVE_ARCH_COMPLEMENT_BIT
00358 L4_INLINE void
00359 l4util_complement_bit(int b, volatile l4_umword_t * dest)
00360 {
00361     dest += b / (sizeof(*dest) * 8);
00362     b    &= sizeof(*dest) * 8 - 1;
00363
00364     *dest ^= 1UL << b;
00365 }
00366 #endif
00367
00368 /*
00369  * Adapted from:
00370  * http://en.wikipedia.org/wiki/Power\_of\_two#Algorithm\_to\_find\_the\_next-highest\_power\_of\_two
00371  */
00372 L4_INLINE int
00373 l4util_next_power2(unsigned long val)
00374 {
00375     unsigned i;
00376
00377     if (val == 0)
00378         return 1;
00379
00380     val--;
00381     for (i=1; i < sizeof(unsigned long)*8; i<=1)
00382         val = val | val >> i;
00383
00384     return val+1;
00385 }
00386
00387
00388 /* Non-implemented version, catch with a linker warning */
00389
00390 extern int __this_l4util_bitops_function_is_not_implemented_for_this_arch__sorry(void);
00391
00392 #ifndef __L4UTIL_BITOPS_HAVE_ARCH_BIT_TEST_AND_COMPLEMENT
00393 L4_INLINE int
00394 l4util_btc(int b, volatile l4_umword_t * dest)
00395 { (void)b; (void)dest; __this_l4util_bitops_function_is_not_implemented_for_this_arch__sorry(); return
00396 0; }
00397 #endif
00398
00399 #ifndef __L4UTIL_BITOPS_HAVE_ARCH_FIND_FIRST_SET_BIT
00400 L4_INLINE int
00401 l4util_find_first_set_bit(const void * dest, l4_size_t size)
00402 { (void)dest; (void)size; __this_l4util_bitops_function_is_not_implemented_for_this_arch__sorry();
00403 return 0; }
00404 #endif
00405 #endif /* ! __L4UTIL__INCLUDE__BITOPS_H__ */

```


## 16.632 l4/util/elf.h File Reference

ELF definition.



```
#include <l4/sys/l4int.h>
```

Include dependency graph for elf.h:



## Data Structures

- struct [Elf32\\_Ehdr](#)  
*ELF32 header.*
- struct [Elf64\\_Ehdr](#)  
*ELF64 header.*
- struct [Elf32\\_Shdr](#)  
*ELF32 section header.*
- struct [Elf64\\_Shdr](#)  
*ELF64 section header.*
- struct [Elf32\\_Phdr](#)  
*ELF32 program header.*
- struct [Elf64\\_Phdr](#)  
*ELF64 program header.*
- struct [Elf32\\_Dyn](#)  
*ELF32 dynamic entry.*
- struct [Elf64\\_Dyn](#)  
*ELF64 dynamic entry.*
- struct [Elf32\\_Rel](#)  
*ELF32 relocation entry w/o addend.*
- struct [Elf32\\_Rela](#)  
*ELF32 relocation entry w/ addend.*
- struct [Elf64\\_Rel](#)  
*ELF64 relocation entry w/o addend.*
- struct [Elf64\\_Rela](#)  
*ELF64 relocation entry w/ addend.*
- struct [Elf32\\_Sym](#)  
*ELF32 symbol table entry.*
- struct [Elf64\\_Sym](#)  
*ELF64 symbol table entry.*

- struct [Elf32\\_Auxv](#)  
*Auxiliary vector (32-bit).*
- struct [Elf64\\_Auxv](#)  
*Auxiliary vector (64-bit).*

## Macros

- #define **ElfW**(type)  
*Use 64 or 32 bits types depending on the target architecture.*
- #define **ELF32\_R\_SYM**(i)  
*Symbol table index.*
- #define **ELF32\_R\_TYPE**(i)
- #define **ELF32\_R\_INFO**(s, t)  
*Create info from symbol table index + type.*
- #define **ELF64\_R\_SYM**(i)  
*Symbol table index.*
- #define **ELF64\_R\_TYPE**(i)
- #define **ELF64\_R\_INFO**(s, t)  
*Create info from symbol table index + type.*
- #define **ELF32\_ST\_BIND**(i)
- #define **ELF32\_ST\_TYPE**(i)
- #define **ELF32\_ST\_INFO**(b, t)  
*Make info from bind + type.*
- #define **ELF64\_ST\_BIND**(i)
- #define **ELF64\_ST\_TYPE**(i)
- #define **ELF64\_ST\_INFO**(b, t)  
*Make info from bind + type.*

## Typedefs

- typedef struct Elf32\_Auxv **Elf32\_Auxv**  
*Auxiliary vector (32-bit).*
- typedef struct Elf64\_Auxv **Elf64\_Auxv**  
*Auxiliary vector (64-bit).*

## ELF types

- typedef [l4\\_uint32\\_t](#) **Elf32\_Addr**  
*size 4 align 4*
- typedef [l4\\_uint32\\_t](#) **Elf32\_Off**  
*size 4 align 4*
- typedef [l4\\_uint16\\_t](#) **Elf32\_Half**  
*size 2 align 2*
- typedef [l4\\_uint32\\_t](#) **Elf32\_Word**  
*size 4 align 4*
- typedef [l4\\_int32\\_t](#) **Elf32\_Sword**  
*size 4 align 4*
- typedef [l4\\_uint64\\_t](#) **Elf64\_Addr**  
*size 8 align 8*
- typedef [l4\\_uint64\\_t](#) **Elf64\_Off**  
*size 8 align 8*
- typedef [l4\\_uint16\\_t](#) **Elf64\_Half**

- size 2 align 2*
- typedef [l4\\_uint32\\_t](#) [Elf64\\_Word](#)
- size 4 align 4*
- typedef [l4\\_int32\\_t](#) [Elf64\\_Sword](#)
- size 4 align 4*
- typedef [l4\\_uint64\\_t](#) [Elf64\\_Xword](#)
- size 8 align 8*
- typedef [l4\\_int64\\_t](#) [Elf64\\_Sxword](#)
- size 8 align 8*

## Enumerations

- enum { [EI\\_NIDENT](#) = 16 }
- enum [Elf\\_ETs](#) {  
[ET\\_NONE](#) = 0 , [ET\\_REL](#) = 1 , [ET\\_EXEC](#) = 2 , [ET\\_DYN](#) = 3 ,  
[ET\\_CORE](#) = 4 , [ET\\_LOPROC](#) = 0xff00 , [ET\\_HIPROC](#) = 0xffff }
- Object file type.*
- enum [Elf\\_EMs](#) {  
[EM\\_NONE](#) = 0 , [EM\\_M32](#) = 1 , [EM\\_SPARC](#) = 2 , [EM\\_386](#) = 3 ,  
[EM\\_68K](#) = 4 , [EM\\_88K](#) = 5 , [EM\\_860](#) = 7 , [EM\\_MIPS](#) = 8 ,  
[EM\\_MIPS\\_RS4\\_BE](#) = 10 , [EM\\_SPARC64](#) = 11 , [EM\\_PARISC](#) = 15 , [EM\\_VPP500](#) = 17 ,  
[EM\\_SPARC32PLUS](#) = 18 , [EM\\_960](#) = 19 , [EM\\_PPC](#) = 20 , [EM\\_V800](#) = 36 ,  
[EM\\_FR20](#) = 37 , [EM\\_RH32](#) = 38 , [EM\\_RCE](#) = 39 , [EM\\_ARM](#) = 40 ,  
[EM\\_ALPHA](#) = 41 , [EM\\_SH](#) = 42 , [EM\\_SPARCV9](#) = 43 , [EM\\_TRICORE](#) = 44 ,  
[EM\\_ARC](#) = 45 , [EM\\_H8\\_300](#) = 46 , [EM\\_H8\\_300H](#) = 47 , [EM\\_H8S](#) = 48 ,  
[EM\\_H8\\_500](#) = 49 , [EM\\_IA\\_64](#) = 50 , [EM\\_MIPS\\_X](#) = 51 , [EM\\_COLDFIRE](#) = 52 ,  
[EM\\_68HC12](#) = 53 , [EM\\_X86\\_64](#) = 62 , [EM\\_PDSP](#) = 63 , [EM\\_FX66](#) = 66 ,  
[EM\\_ST9PLUS](#) = 67 , [EM\\_ST7](#) = 68 , [EM\\_68HC16](#) = 69 , [EM\\_68HC11](#) = 70 ,  
[EM\\_68HC08](#) = 71 , [EM\\_68HC05](#) = 72 , [EM\\_SVX](#) = 73 , [EM\\_ST19](#) = 74 ,  
[EM\\_VAX](#) = 75 , [EM\\_CRIS](#) = 76 , [EM\\_JAVELIN](#) = 77 , [EM\\_FIREPATH](#) = 78 ,  
[EM\\_ZSP](#) = 79 , [EM\\_MMIX](#) = 80 , [EM\\_HUANY](#) = 81 , [EM\\_PRISM](#) = 82 ,  
[EM\\_AVR](#) = 83 , [EM\\_FR30](#) = 84 , [EM\\_D10V](#) = 85 , [EM\\_D30V](#) = 86 ,  
[EM\\_V850](#) = 87 , [EM\\_M32R](#) = 88 , [EM\\_MN10300](#) = 89 , [EM\\_MN10200](#) = 90 ,  
[EM\\_PJ](#) = 91 , [EM\\_OPENRISC](#) = 92 , [EM\\_ARC\\_A5](#) = 93 , [EM\\_XTENSA](#) = 94 ,  
[EM\\_ALTERA\\_NIOS2](#) = 113 , [EM\\_AARCH64](#) = 183 , [EM\\_TILEPRO](#) = 188 , [EM\\_MICROBLAZE](#) = 189 ,  
[EM\\_TILEGX](#) = 191 , [EM\\_RISCV](#) = 243 , [EM\\_NUM](#) = 244 }
- Required architecture.*
- enum [Elf\\_EVs](#) { [EV\\_NONE](#) = 0 , [EV\\_CURRENT](#) = 1 }
- Object file version.*
- enum [Elf\\_EIs](#) {  
[EI\\_MAG0](#) = 0 , [EI\\_MAG1](#) = 1 , [EI\\_MAG2](#) = 2 , [EI\\_MAG3](#) = 3 ,  
[EI\\_CLASS](#) = 4 , [EI\\_DATA](#) = 5 , [EI\\_VERSION](#) = 6 , [EI\\_OSABI](#) = 7 ,  
[EI\\_ABIVERSION](#) = 8 , [EI\\_PAD](#) = 9 }
- Identification Indices.*
- enum [Elf\\_MAGs](#) { [ELFMAG0](#) = 0x7f , [ELFMAG1](#) = 'E' , [ELFMAG2](#) = 'L' , [ELFMAG3](#) = 'F' }
- Magic number.*
- enum [Elf\\_CIASSs](#) { [ELFCLASSNONE](#) = 0 , [ELFCLASS32](#) = 1 , [ELFCLASS64](#) = 2 , [ELFCLASSNUM](#) = 3 }
- File class or capacity.*
- enum [Elf\\_DATAs](#) { [ELFDATANONE](#) = 0 , [ELFDATA2LSB](#) = 1 , [ELFDATA2MSB](#) = 2 , [ELFDATANUM](#) = 3 }
- Data encoding.*
- enum [Elf\\_OSABIs](#) {  
[ELFOSABI\\_NONE](#) = 0 , [ELFOSABI\\_SYSV](#) = 0 , [ELFOSABI\\_HPUX](#) = 1 , [ELFOSABI\\_NETBSD](#) = 2 ,  
[ELFOSABI\\_LINUX](#) = 3 , [ELFOSABI\\_SOLARIS](#) = 6 , [ELFOSABI\\_AIX](#) = 7 , [ELFOSABI\\_IRIX](#) = 8 ,  
[ELFOSABI\\_FREEBSD](#) = 9 , [ELFOSABI\\_TRU64](#) = 10 , [ELFOSABI\\_MODESTO](#) = 11 , [ELFOSABI\\_OPENBSD](#)  
= 12 ,  
[ELFOSABI\\_ARM](#) = 97 , [ELFOSABI\\_STANDALONE](#) = 255 }

*Identify operating system and ABI to which the object is targeted.*

- enum `Elf_SHNs` {  
`SHN_UNDEF` = 0 , `SHN_LORESERVE` = 0xff00 , `SHN_LOPROC` = 0xff00 , `SHN_HIPROC` = 0xff1f ,  
`SHN_ABS` = 0xffff , `SHN_COMMON` = 0xffff2 , `SHN_HIRESERVE` = 0xffff }

*Special section indexes.*

- enum `Elf_SHTs` {  
`SHT_NULL` = 0 , `SHT_PROGBITS` = 1 , `SHT_SYMTAB` = 2 , `SHT_STRTAB` = 3 ,  
`SHT_RELA` = 4 , `SHT_HASH` = 5 , `SHT_DYNAMIC` = 6 , `SHT_NOTE` = 7 ,  
`SHT_NOBITS` = 8 , `SHT_REL` = 9 , `SHT_SHLIB` = 10 , `SHT_DYNSYM` = 11 ,  
`SHT_INIT_ARRAY` = 14 , `SHT_FINI_ARRAY` = 15 , `SHT_PREINIT_ARRAY` = 16 , `SHT_GROUP` = 17 ,  
`SHT_SYMTAB_SHNDX` = 18 , `SHT_NUM` = 19 , `SHT_LOOS` = 0x60000000 , `SHT_HIOS` = 0x6fffffff ,  
`SHT_LOPROC` = 0x70000000 , `SHT_HIPROC` = 0x7fffffff , `SHT_LOUSER` = 0x80000000 , `SHT_HIUSER` =  
0xffffffff }

*Section type.*

- enum `Elf_SHFs` {  
`SHF_WRITE` = 0x1 , `SHF_ALLOC` = 0x2 , `SHF_EXECINSTR` = 0x4 , `SHF_MERGE` = 0x10 ,  
`SHF_STRINGS` = 0x20 , `SHF_INFO_LINK` = 0x40 , `SHF_LINK_ORDER` = 0x80 , `SHF_OS_NONCONFORMING`  
= 0x100 ,  
`SHF_GROUP` = 0x200 , `SHF_TLS` = 0x400 , `SHF_MASKOS` = 0x0ff00000 , `SHF_MASKPROC` = 0xf0000000  
}

*Section attribute flags.*

- enum `Elf_PTs` {  
`PT_NULL` = 0 , `PT_LOAD` = 1 , `PT_DYNAMIC` = 2 , `PT_INTERP` = 3 ,  
`PT_NOTE` = 4 , `PT_SHLIB` = 5 , `PT_PHDR` = 6 , `PT_TLS` = 7 ,  
`PT_NUM` = 8 , `PT_LOOS` = 0x60000000 , `PT_HIOS` = 0x6fffffff , `PT_LOPROC` = 0x70000000 ,  
`PT_HIPROC` = 0x7fffffff , `PT_GNU_EH_FRAME` = `PT_LOOS` + 0x474e550 , `PT_GNU_STACK` = `PT_LOOS`  
+ 0x474e551 , `PT_GNU_RELRO` = `PT_LOOS` + 0x474e552 ,  
`PT_L4_STACK` = `PT_LOOS` + 0x12 , `PT_L4_AUX` = `PT_LOOS` + 0x14 }

*Segment types.*

- enum `Elf_PFs` {  
`PF_X` = 0x1 , `PF_W` = 0x2 , `PF_R` = 0x4 , `PF_MASKOS` = 0x0ff00000 ,  
`PF_MASKPROC` = 0x7fffffff }

*Segment permissions.*

- enum `Elf_NT_s_core` {  
`NT_PRSTATUS` = 1 , `NT_FPREGSET` = 2 , `NT_PRPSINFO` = 3 , `NT_PRXREG` = 4 ,  
`NT_TASKSTRUCT` = 4 , `NT_PLATFORM` = 5 , `NT_AUXV` = 6 , `NT_GWINDOWS` = 7 ,  
`NT_ASRS` = 8 , `NT_PSTATUS` = 10 , `NT_PSINFO` = 13 , `NT_PRCRED` = 14 ,  
`NT_UTSNAME` = 15 , `NT_LWPSTATUS` = 16 , `NT_LWPSINFO` = 17 , `NT_PRFPXREG` = 20 }

*Legal values for note segment descriptor types for core files.*

- enum `Elf_NT_s_obj` { `NT_VERSION` = 1 }

*Legal values for the note segment descriptor types for object files.*

- enum `Elf_DT_s` {  
`DT_NULL` = 0 , `DT_NEEDED` = 1 , `DT_PLTRELSZ` = 2 , `DT_PLTGOT` = 3 ,  
`DT_HASH` = 4 , `DT_STRTAB` = 5 , `DT_SYMTAB` = 6 , `DT_RELA` = 7 ,  
`DT_RELASZ` = 8 , `DT_RELAENT` = 9 , `DT_STRSZ` = 10 , `DT_SYMENT` = 11 ,  
`DT_INIT` = 12 , `DT_FINI` = 13 , `DT_SONAME` = 14 , `DT_RPATH` = 15 ,  
`DT_SYMBOLIC` = 16 , `DT_REL` = 17 , `DT_RELSZ` = 18 , `DT_RELENT` = 19 ,  
`DT_PTRREL` = 20 , `DT_DEBUG` = 21 , `DT_TEXTREL` = 22 , `DT_JMPREL` = 23 ,  
`DT_BIND_NOW` = 24 , `DT_INIT_ARRAY` = 25 , `DT_FINI_ARRAY` = 26 , `DT_INIT_ARRAYSZ` = 27 ,  
`DT_FINI_ARRAYSZ` = 28 , `DT_RUNPATH` = 29 , `DT_FLAGS` = 30 , `DT_ENCODING` = 32 ,  
`DT_PREINIT_ARRAY` = 32 , `DT_PREINIT_ARRAYSZ` = 33 , `DT_NUM` = 34 , `DT_LOOS` = 0x60000000 ,  
`DT_HIOS` = 0x6fffffff , `DT_LOPROC` = 0x70000000 , `DT_HIPROC` = 0x7fffffff }

*Dynamic Array Tags.*

- enum `Elf_DFs` {  
`DF_ORIGIN` = 0x00000001 , `DF_SYMBOLIC` = 0x00000002 , `DF_TEXTREL` = 0x00000004 ,  
`DF_BIND_NOW` = 0x00000008 ,  
`DF_STATIC_TLS` = 0x00000010 }

Values of *Elf32\_Dyn.d\_un.d\_val*, *Elf64\_Dyn.d\_un.d\_val* in the *DT\_FLAGS* entry.

- enum [Elf\\_DF\\_1s](#) {  
[DF\\_1\\_NOW](#) = 0x00000001 , [DF\\_1\\_GLOBAL](#) = 0x00000002 , [DF\\_1\\_GROUP](#) = 0x00000004 ,  
[DF\\_1\\_NODELETE](#) = 0x00000008 ,  
[DF\\_1\\_LOADFLTR](#) = 0x00000010 , [DF\\_1\\_INITFIRST](#) = 0x00000020 , [DF\\_1\\_NOOPEN](#) = 0x00000040 ,  
[DF\\_1\\_ORIGIN](#) = 0x00000080 ,  
[DF\\_1\\_DIRECT](#) = 0x00000100 , [DF\\_1\\_TRANS](#) = 0x00000200 , [DF\\_1\\_INTERPOSE](#) = 0x00000400 ,  
[DF\\_1\\_NODEFLIB](#) = 0x00000800 ,  
[DF\\_1\\_NODUMP](#) = 0x00001000 , [DF\\_1\\_CONFALT](#) = 0x00002000 , [DF\\_1\\_ENDFILTEE](#) = 0x00004000 ,  
[DF\\_1\\_DISPRELDNE](#) = 0x00008000 ,  
[DF\\_1\\_DISPRELPND](#) = 0x00010000 }

State flags selectable in the *Elf32\_Dyn.d\_un.d\_val* / *Elf64\_Dyn.d\_un.d\_val* element of the *DT\_FLAGS\_1* entry in the dynamic section.

- enum [Elf\\_DTF\\_1s](#)

Flags for the feature selection in *DT\_FEATURE\_1*.

- enum [Elf\\_DF\\_P1s](#) { [DF\\_P1\\_LAZYLOAD](#) = 0x00000001 , [DF\\_P1\\_GROUPPERM](#) = 0x00000002 }

Flags in the *DT\_POSFLAG\_1* entry effecting only the next *DT\_\** entry.

- enum [Elf\\_R\\_386\\_s](#) {  
[R\\_386\\_NONE](#) = 0 , [R\\_386\\_32](#) = 1 , [R\\_386\\_PC32](#) = 2 , [R\\_386\\_GOT32](#) = 3 ,  
[R\\_386\\_PLT32](#) = 4 , [R\\_386\\_COPY](#) = 5 , [R\\_386\\_GLOB\\_DAT](#) = 6 , [R\\_386\\_JMP\\_SLOT](#) = 7 ,  
[R\\_386\\_RELATIVE](#) = 8 , [R\\_386\\_GOTOFF](#) = 9 , [R\\_386\\_GOTPC](#) = 10 , [R\\_386\\_32PLT](#) = 11 ,  
[R\\_386\\_TLS\\_TPOFF](#) = 14 , [R\\_386\\_TLS\\_IE](#) = 15 , [R\\_386\\_TLS\\_GOTIE](#) = 16 , [R\\_386\\_TLS\\_LE](#) = 17 ,  
[R\\_386\\_TLS\\_GD](#) = 18 , [R\\_386\\_TLS\\_LDM](#) = 19 , [R\\_386\\_16](#) = 20 , [R\\_386\\_PC16](#) = 21 ,  
[R\\_386\\_8](#) = 22 , [R\\_386\\_PC8](#) = 23 , [R\\_386\\_TLS\\_GD\\_32](#) = 24 , [R\\_386\\_TLS\\_GD\\_PUSH](#) = 25 ,  
[R\\_386\\_TLS\\_GD\\_CALL](#) = 26 , [R\\_386\\_TLS\\_GD\\_POP](#) = 27 , [R\\_386\\_TLS\\_LDM\\_32](#) = 28 , [R\\_386\\_TLS\\_LDM\\_PUSH](#)  
= 29 ,  
[R\\_386\\_TLS\\_LDM\\_CALL](#) = 30 , [R\\_386\\_TLS\\_LDM\\_POP](#) = 31 , [R\\_386\\_TLS\\_LDO\\_32](#) = 32 , [R\\_386\\_TLS\\_IE\\_32](#)  
= 33 ,  
[R\\_386\\_TLS\\_LE\\_32](#) = 34 , [R\\_386\\_TLS\\_DTPMOD32](#) = 35 , [R\\_386\\_TLS\\_DTPOFF32](#) = 36 , [R\\_386\\_TLS\\_TPOFF32](#)  
= 37 ,  
[R\\_386\\_NUM](#) = 38 }

Relocation types (processor specific).

- enum [Elf\\_EF\\_ARM\\_s](#) { }

ARM specific declarations.

- enum [Elf\\_STT\\_ARM\\_s](#)

Additional symbol types for Thumb.

- enum [Elf\\_SHF\\_s\\_ARM](#) { [SHF\\_ARM\\_ENTRYSECT](#) = 0x10000000 , [SHF\\_ARM\\_COMDEF](#) = 0x80000000 }

ARM-specific values for *Elf32\_Shdr.sh\_flags* / *Elf64\_Shdr.sh\_flags*.

- enum [Elf\\_ARM\\_SBs](#) { [PF\\_ARM\\_SB](#) = 0x10000000 }

ARM-specific program header flags.

- enum [Elf\\_R\\_ARM\\_s](#) {  
[R\\_ARM\\_NONE](#) = 0 , [R\\_ARM\\_PC24](#) = 1 , [R\\_ARM\\_ABS32](#) = 2 , [R\\_ARM\\_REL32](#) = 3 ,  
[R\\_ARM\\_PC13](#) = 4 , [R\\_ARM\\_ABS16](#) = 5 , [R\\_ARM\\_ABS12](#) = 6 , [R\\_ARM\\_THM\\_ABS5](#) = 7 ,  
[R\\_ARM\\_ABS8](#) = 8 , [R\\_ARM\\_SBREL32](#) = 9 , [R\\_ARM\\_THM\\_PC22](#) = 10 , [R\\_ARM\\_THM\\_PC8](#) = 11 ,  
[R\\_ARM\\_AMP\\_VCALL9](#) = 12 , [R\\_ARM\\_SWI24](#) = 13 , [R\\_ARM\\_THM\\_SWI8](#) = 14 , [R\\_ARM\\_XPC25](#) = 15 ,  
[R\\_ARM\\_THM\\_XPC22](#) = 16 , [R\\_ARM\\_COPY](#) = 20 , [R\\_ARM\\_GLOB\\_DAT](#) = 21 , [R\\_ARM\\_JUMP\\_SLOT](#) = 22 ,  
[R\\_ARM\\_RELATIVE](#) = 23 , [R\\_ARM\\_GOTOFF](#) = 24 , [R\\_ARM\\_GOTPC](#) = 25 , [R\\_ARM\\_GOT32](#) = 26 ,  
[R\\_ARM\\_PLT32](#) = 27 , [R\\_ARM\\_ALU\\_PCREL\\_7\\_0](#) = 32 , [R\\_ARM\\_ALU\\_PCREL\\_15\\_8](#) = 33 , [R\\_ARM\\_↵](#)  
[ALU\\_PCREL\\_23\\_15](#) = 34 ,  
[R\\_ARM\\_LDR\\_SBREL\\_11\\_0](#) = 35 , [R\\_ARM\\_ALU\\_SBREL\\_19\\_12](#) = 36 , [R\\_ARM\\_ALU\\_SBREL\\_27\\_20](#) =  
37 , [R\\_ARM\\_GNU\\_VTENTRY](#) = 100 ,  
[R\\_ARM\\_GNU\\_VTINHERIT](#) = 101 , [R\\_ARM\\_THM\\_PC11](#) = 102 , [R\\_ARM\\_THM\\_PC9](#) = 103 , [R\\_ARM\\_↵](#)  
[RXPC25](#) = 249 ,  
[R\\_ARM\\_RSBREL32](#) = 250 , [R\\_ARM\\_THM\\_RPC22](#) = 251 , [R\\_ARM\\_RREL32](#) = 252 , [R\\_ARM\\_RABS22](#) =  
253 ,  
[R\\_ARM\\_RPC24](#) = 254 , [R\\_ARM\\_RBASE](#) = 255 , [R\\_ARM\\_NUM](#) = 256 }

*ARM relocations.*

- enum `Elf_R_AARCH64_s` { `R_AARCH64_NONE` = 0 , `R_AARCH64_RELATIVE` = 1027 }

*AARCH64 relocations.*

- enum `Elf_R_X86_64_s` {  
`R_X86_64_NONE` = 0 , `R_X86_64_64` = 1 , `R_X86_64_PC32` = 2 , `R_X86_64_GOT32` = 3 ,  
`R_X86_64_PLT32` = 4 , `R_X86_64_COPY` = 5 , `R_X86_64_GLOB_DAT` = 6 , `R_X86_64_JUMP_SLOT` = 7 ,  
`R_X86_64_RELATIVE` = 8 , `R_X86_64_GOTPCREL` = 9 , `R_X86_64_32` = 10 , `R_X86_64_32S` = 11 ,  
`R_X86_64_16` = 12 , `R_X86_64_PC16` = 13 , `R_X86_64_8` = 14 , `R_X86_64_PC8` = 15 ,  
`R_X86_64_DTPMOD64` = 16 , `R_X86_64_DTPOFF64` = 17 , `R_X86_64_TPOFF64` = 18 , `R_X86_64_TLSGD`  
= 19 ,  
`R_X86_64_TLSLD` = 20 , `R_X86_64_DTPOFF32` = 21 , `R_X86_64_GOTTPOFF` = 22 , `R_X86_64_TPOFF32`  
= 23 ,  
`R_X86_64_NUM` = 24 }

*AMD x86-64 relocations.*

- enum `Elf_STNs`

*Symbol Table Entry.*

- enum `Elf_STBs` {  
`STB_LOCAL` = 0 , `STB_GLOBAL` = 1 , `STB_WEAK` = 2 , `STB_LOOS` = 10 ,  
`STB_HIOS` = 12 , `STB_LOPROC` = 13 , `STB_HIPROC` = 15 }

*Symbol Binding.*

- enum `Elf_STTs` {  
`STT_NOTYPE` = 0 , `STT_OBJECT` = 1 , `STT_FUNC` = 2 , `STT_SECTION` = 3 ,  
`STT_FILE` = 4 , `STT_LOOS` = 10 , `STT_HIOS` = 12 , `STT_LOPROC` = 13 ,  
`STT_HIPROC` = 15 }

*Symbol Types.*

- enum `Elf_ATs` {  
`AT_NULL` = 0 , `AT_IGNORE` = 1 , `AT_EXECFD` = 2 , `AT_PHDR` = 3 ,  
`AT_PHENT` = 4 , `AT_PHNUM` = 5 , `AT_PAGESZ` = 6 , `AT_BASE` = 7 ,  
`AT_FLAGS` = 8 , `AT_ENTRY` = 9 , `AT_NOTELF` = 10 , `AT_UID` = 11 ,  
`AT_EUID` = 12 , `AT_GID` = 13 , `AT_EGID` = 14 , `AT_L4_AUX` = 0xf0 ,  
`AT_L4_ENV` = 0xf1 , `AT_L4_KIP` = 0xf2 }

*Legal values for `Elf32_Auxv.atype` / `Elf64_Auxv.atype`.*

## 16.632.1 Detailed Description

ELF definition.

Date

08/18/2000

Author

Frank Mehnert [fm3@os.inf.tu-dresden.de](mailto:fm3@os.inf.tu-dresden.de) Alexander Warg [aw11@os.inf.tu-dresden.de](mailto:aw11@os.inf.tu-dresden.de)

Many structs from "Executable and Linkable Format (ELF)", Portable Formats Specification, Version 1.1 and "↵ System V Application Binary Interface - DRAFT - April 29, 1998" The Santa Cruz Operation, Inc. (see [http↵://www.sco.com/developer/gabi/contents.html](http://www.sco.com/developer/gabi/contents.html))

Definition in file `elf.h`.

## 16.633 elf.h

[Go to the documentation of this file.](#)

```

00001
00019 /*
00020  * (c) 2008-2009 Author(s)
00021  *     economic rights: Technische Universität Dresden (Germany)
00022  * License: see LICENSE.spdx (in this directory or the directories above)
00023  */
00024
00025 /* (c) 2003-2006 Technische Universitaet Dresden
00026  * License: see LICENSE.spdx (in this directory or the directories above) */
00027
00028 #pragma once
00029
00030 #include <l4/sys/l4int.h>
00031
00037
00042 typedef l4_uint32_t      Elf32_Addr;
00043 typedef l4_uint32_t      Elf32_Off;
00044 typedef l4_uint16_t      Elf32_Half;
00045 typedef l4_uint32_t      Elf32_Word;
00046 typedef l4_int32_t       Elf32_Sword;
00047 typedef l4_uint64_t      Elf64_Addr;
00048 typedef l4_uint64_t      Elf64_Off;
00049 typedef l4_uint16_t      Elf64_Half;
00050 typedef l4_uint32_t      Elf64_Word;
00051 typedef l4_int32_t       Elf64_Sword;
00052 typedef l4_uint64_t      Elf64_Xword;
00053 typedef l4_int64_t       Elf64_Sxword;
00055
00060 #if L4_MWORD_BITS == 64
00061 # define ElfW(type)      _ElfW(Elf, 64, type)
00062 #else
00063 # define ElfW(type)      _ElfW(Elf, 32, type)
00064 #endif
00065 #define _ElfW(e,w,t)      __ElfW(e, w, _##t)
00066 #define __ElfW(e,w,t)    e##w##t
00067
00068 #if defined(ARCH_x86)
00069 # define L4_ARCH_EI_DATA      ELFDATA2LSB
00070 # define L4_ARCH_E_MACHINE    EM_386
00071 # define L4_ARCH_EI_CLASS     ELFCLASS32
00072 #elif defined(ARCH_amd64)
00073 # define L4_ARCH_EI_DATA      ELFDATA2LSB
00074 # define L4_ARCH_E_MACHINE    EM_X86_64
00075 # define L4_ARCH_EI_CLASS     ELFCLASS64
00076 #elif defined(ARCH_arm)
00077 # define L4_ARCH_EI_DATA      ELFDATA2LSB
00078 # define L4_ARCH_E_MACHINE    EM_ARM
00079 # define L4_ARCH_EI_CLASS     ELFCLASS32
00080 #elif defined(ARCH_arm64)
00081 # define L4_ARCH_EI_DATA      ELFDATA2LSB
00082 # define L4_ARCH_E_MACHINE    EM_AARCH64
00083 # define L4_ARCH_EI_CLASS     ELFCLASS64
00084 #elif defined(ARCH_ppc32)
00085 # define L4_ARCH_EI_DATA      ELFDATA2MSB
00086 # define L4_ARCH_E_MACHINE    EM_PPC
00087 # define L4_ARCH_EI_CLASS     ELFCLASS32
00088 #elif defined(ARCH_sparc)
00089 # define L4_ARCH_EI_DATA      ELFDATA2MSB
00090 # define L4_ARCH_E_MACHINE    EM_SPARC
00091 # define L4_ARCH_EI_CLASS     ELFCLASS32
00092 #elif defined(ARCH_mips)
00093 # define L4_ARCH_EI_DATA      ELFDATA2LSB
00094 # define L4_ARCH_E_MACHINE    EM_MIPS
00095 # ifdef __mips64
00096 #   define L4_ARCH_EI_CLASS     ELFCLASS64
00097 # else
00098 #   define L4_ARCH_EI_CLASS     ELFCLASS32
00099 # endif
00100 #elif defined(ARCH_riscv)
00101 # define L4_ARCH_EI_DATA      ELFDATA2LSB
00102 # define L4_ARCH_E_MACHINE    EM_RISCV
00103 # if __riscv_xlen == 64
00104 #   define L4_ARCH_EI_CLASS     ELFCLASS64
00105 # else
00106 #   define L4_ARCH_EI_CLASS     ELFCLASS32
00107 # endif
00108 #else
00109 # warning elf.h: Unsupported build architecture!
00110 #endif
00111
00112
00114

```

```

00116
00117 enum
00118 {
00119     EI_NIDENT          = 16,
00120 };
00121
00125 typedef struct
00126 {
00127     unsigned char e_ident[EI_NIDENT];
00128     Elf32_Half    e_type;
00129     Elf32_Half    e_machine;
00130     Elf32_Word    e_version;
00131     Elf32_Addr    e_entry;
00132     Elf32_Off     e_phoff;
00133     Elf32_Off     e_shoff;
00134     Elf32_Word    e_flags;
00135     Elf32_Half    e_ehsize;
00136     Elf32_Half    e_phentsize;
00137     Elf32_Half    e_phnum;
00138     Elf32_Half    e_shentsize;
00139     Elf32_Half    e_shnum;
00140     Elf32_Half    e_shstrndx;
00141 } Elf32_Ehdr;
00142
00146 typedef struct
00147 {
00148     unsigned char e_ident[EI_NIDENT];
00149     Elf64_Half    e_type;
00150     Elf64_Half    e_machine;
00151     Elf64_Word    e_version;
00152     Elf64_Addr    e_entry;
00153     Elf64_Off     e_phoff;
00154     Elf64_Off     e_shoff;
00155     Elf64_Word    e_flags;
00156     Elf64_Half    e_ehsize;
00157     Elf64_Half    e_phentsize;
00158     Elf64_Half    e_phnum;
00159     Elf64_Half    e_shentsize;
00160     Elf64_Half    e_shnum;
00161     Elf64_Half    e_shstrndx;
00162 } Elf64_Ehdr;
00163
00168 enum Elf_ETs
00169 {
00170     ET_NONE          = 0,
00171     ET_REL           = 1,
00172     ET_EXEC          = 2,
00173     ET_DYN           = 3,
00174     ET_CORE          = 4,
00175     ET_LOPROC        = 0xff00,
00176     ET_HIPROC        = 0xffff,
00177 };
00178
00183 enum Elf_EMs
00184 {
00185     EM_NONE          = 0,
00186     EM_M32           = 1,
00187     EM_SPARC         = 2,
00188     EM_386           = 3,
00189     EM_68K           = 4,
00190     EM_88K           = 5,
00191     EM_860           = 7,
00192     EM_MIPS          = 8,
00193     EM_MIPS_RS4_BE   = 10,
00194     EM_SPARC64       = 11,
00195     EM_PARISC        = 15,
00196     EM_VPP500        = 17,
00197     EM_SPARC32PLUS   = 18,
00198     EM_960           = 19,
00199     EM_PPC           = 20,
00200     EM_V800          = 36,
00201     EM_FR20          = 37,
00202     EM_RH32          = 38,
00203     EM_RCE           = 39,
00204     EM_ARM           = 40,
00205     EM_ALPHA         = 41,
00206     EM_SH            = 42,
00207     EM_SPARCV9       = 43,
00208     EM_TRICORE       = 44,
00209     EM_ARC           = 45,
00210     EM_H8_300        = 46,
00211     EM_H8_300H       = 47,
00212     EM_H8S           = 48,
00213     EM_H8_500        = 49,
00214     EM_IA_64         = 50,
00215     EM_MIPS_X        = 51,
00216     EM_COLDFIRE      = 52,

```



```

00217 EM_68HC12           = 53,
00218 EM_X86_64           = 62,
00219 EM_PDSP             = 63,
00220 EM_FX66              = 66,
00221 EM_ST9PLUS          = 67,
00222 EM_ST7              = 68,
00223 EM_68HC16           = 69,
00224 EM_68HC11          = 70,
00225 EM_68HC08          = 71,
00226 EM_68HC05          = 72,
00227 EM_SVX             = 73,
00228 EM_ST19           = 74,
00229 EM_VAX              = 75,
00230 EM_CRIS              = 76,
00231 EM_JAVELIN          = 77,
00232 EM_FIREPATH         = 78,
00233 EM_ZSP              = 79,
00234 EM_MMIX            = 80,
00235 EM_HUANY            = 81,
00236 EM_PRISM            = 82,
00237 EM_AVR              = 83,
00238 EM_FR30             = 84,
00239 EM_D10V             = 85,
00240 EM_D30V             = 86,
00241 EM_V850            = 87,
00242 EM_M32R             = 88,
00243 EM_MN10300          = 89,
00244 EM_MN10200          = 90,
00245 EM_PJ               = 91,
00246 EM_OPENRISC        = 92,
00247 EM_ARC_A5          = 93,
00248 EM_XTENSA           = 94,
00249 EM_ALTERA_NIOS2     = 113,
00250 EM_AARCH64          = 183,
00251 EM_TILEPRO          = 188,
00252 EM_MICROBLAZE       = 189,
00253 EM_TILEGX           = 191,
00254 EM_RISCV           = 243,
00255 EM_NUM              = 244,
00256 };
00257
00258 #if 0
00259 #define EM_ALPHA       0x9026 /* interim value used by Linux until the
00260                               committee comes up with a final number */
00261 #define EM_S390        0xA390 /* interim value used for IBM S390 */
00262 #endif
00263
00266 enum Elf_EVs
00267 {
00268     EV_NONE           = 0,
00269     EV_CURRENT        = 1,
00270 };
00271
00274 enum Elf_EIs
00275 {
00276     EI_MAG0           = 0,
00277     EI_MAG1           = 1,
00278     EI_MAG2           = 2,
00279     EI_MAG3           = 3,
00280     EI_CLASS          = 4,
00281     EI_DATA           = 5,
00282     EI_VERSION        = 6,
00283     EI_OSABI          = 7,
00284     EI_ABIVERSION     = 8,
00285     EI_PAD            = 9,
00286 };
00287
00289 enum Elf_MAGs
00290 {
00291     ELFMAG0           = 0x7f,
00292     ELFMAG1           = 'E',
00293     ELFMAG2           = 'L',
00294     ELFMAG3           = 'F',
00295 };
00296
00298 enum Elf_CLASSs
00299 {
00300     ELFCLASSNONE      = 0,
00301     ELFCLASS32        = 1,
00302     ELFCLASS64        = 2,
00303     ELFCLASSNUM       = 3,
00304 };
00305
00307 enum Elf_DATAs
00308 {
00309     ELFDATANONE       = 0,
00310     ELFDATA2LSB      = 1,

```

```

00311     ELFDATA2MSB           = 2,
00312     ELFDATANUM           = 3,
00313 };
00314
00316 enum Elf_OSABIs
00317 {
00318     ELFOSABI_NONE           = 0,
00319     ELFOSABI_SYSV           = 0,
00320     ELFOSABI_HPUX           = 1,
00321     ELFOSABI_NETBSD         = 2,
00322     ELFOSABI_LINUX          = 3,
00323     ELFOSABI_SOLARIS        = 6,
00324     ELFOSABI_AIX            = 7,
00325     ELFOSABI_IRIX           = 8,
00326     ELFOSABI_FREEBSD        = 9,
00327     ELFOSABI_TRU64          = 10,
00328     ELFOSABI_MODESTO        = 11,
00329     ELFOSABI_OPENBSD        = 12,
00330     ELFOSABI_ARM            = 97,
00331     ELFOSABI_STANDALONE     = 255,
00332 };
00333
00335 enum Elf_SHNs
00336 {
00337     SHN_UNDEF               = 0,
00338     SHN_LORESERVE           = 0xffff,
00339     SHN_LOPROC              = 0xffff,
00340     SHN_HIPROC              = 0xffff,
00341     SHN_ABS                 = 0xffff,
00342     SHN_COMMON              = 0xffff,
00343     SHN_HIRESERVE           = 0xffff,
00344 };
00345
00347 typedef struct
00348 {
00349     Elf32_Word             sh_name;
00350     Elf32_Word             sh_type;
00351     Elf32_Word             sh_flags;
00352     Elf32_Addr             sh_addr;
00353     Elf32_Off              sh_offset;
00354     Elf32_Word             sh_size;
00355     Elf32_Word             sh_link;
00356     Elf32_Word             sh_info;
00357     Elf32_Word             sh_addralign;
00358     Elf32_Word             sh_entsize;
00359 } Elf32_Shdr;
00360
00362 typedef struct
00363 {
00364     Elf64_Word             sh_name;
00365     Elf64_Word             sh_type;
00366     Elf64_Xword            sh_flags;
00367     Elf64_Addr             sh_addr;
00368     Elf64_Off              sh_offset;
00369     Elf64_Xword            sh_size;
00370     Elf64_Word             sh_link;
00371     Elf64_Word             sh_info;
00372     Elf64_Xword            sh_addralign;
00373     Elf64_Xword            sh_entsize;
00374 } Elf64_Shdr;
00375
00377 enum Elf_SHTs
00378 {
00379     SHT_NULL                = 0,
00380     SHT_PROGBITS            = 1,
00381     SHT_SYMTAB              = 2,
00382     SHT_STRTAB              = 3,
00383     SHT_RELA                = 4,
00384     SHT_HASH                = 5,
00385     SHT_DYNAMIC              = 6,
00386     SHT_NOTE                = 7,
00387     SHT_NOBITS              = 8,
00388     SHT_REL                 = 9,
00389     SHT_SHLIB               = 10,
00390     SHT_DYNSYM              = 11,
00391     SHT_INIT_ARRAY          = 14,
00392     SHT_FINI_ARRAY          = 15,
00393     SHT_PREINIT_ARRAY       = 16,
00394     SHT_GROUP                = 17,
00395     SHT_SYMTAB_SHNDX        = 18,
00396     SHT_NUM                  = 19,
00397     SHT_LOOS                = 0x60000000,
00398     SHT_HIOS                = 0xffffffff,
00399     SHT_LOPROC              = 0x70000000,
00400     SHT_HIPROC              = 0x7fffffff,
00401     SHT_LOUSER              = 0x80000000,
00402     SHT_HIUSER              = 0xffffffff,

```

```

00403 };
00404
00406 enum Elf_SHFs
00407 {
00408     SHF_WRITE           = 0x1,
00409     SHF_ALLOC           = 0x2,
00410     SHF_EXECINSTR       = 0x4,
00411     SHF_MERGE           = 0x10,
00412     SHF_STRINGS         = 0x20,
00413     SHF_INFO_LINK       = 0x40,
00414     SHF_LINK_ORDER      = 0x80,
00415     SHF_OS_NONCONFORMING = 0x100,
00417     SHF_GROUP           = 0x200,
00418     SHF_TLS             = 0x400,
00419     SHF_MASKOS          = 0x0ff00000,
00420     SHF_MASKPROC        = 0xf0000000,
00421 };
00422
00423
00425 typedef struct
00426 {
00427     Elf32_Word    p_type;
00428     Elf32_Off     p_offset;
00429     Elf32_Addr    p_vaddr;
00430     Elf32_Addr    p_paddr;
00431     Elf32_Word    p_filesz;
00432     Elf32_Word    p_memsz;
00433     Elf32_Word    p_flags;
00434     Elf32_Word    p_align;
00435 } Elf32_Phdr;
00436
00438 typedef struct
00439 {
00440     Elf64_Word    p_type;
00441     Elf64_Word    p_flags;
00442     Elf64_Off     p_offset;
00443     Elf64_Addr    p_vaddr;
00444     Elf64_Addr    p_paddr;
00445     Elf64_Xword   p_filesz;
00446     Elf64_Xword   p_memsz;
00447     Elf64_Xword   p_align;
00448 } Elf64_Phdr;
00449
00451 enum Elf_PTs
00452 {
00453     PT_NULL           = 0,
00454     PT_LOAD           = 1,
00455     PT_DYNAMIC        = 2,
00456     PT_INTERP         = 3,
00457     PT_NOTE           = 4,
00458     PT_SHLIB          = 5,
00459     PT_PHDR           = 6,
00460     PT_TLS            = 7,
00461     PT_NUM            = 8,
00462     PT_LOOS           = 0x60000000,
00463     PT_HIOS           = 0x6fffffff,
00464     PT_LOPROC         = 0x70000000,
00465     PT_HIPROC         = 0x7fffffff,
00466
00467     PT_GNU_EH_FRAME   = PT_LOOS + 0x474e550,
00468     PT_GNU_STACK      = PT_LOOS + 0x474e551,
00469     PT_GNU_RELRO      = PT_LOOS + 0x474e552,
00470
00471     PT_L4_STACK       = PT_LOOS + 0x12,
00472     PT_L4_AUX         = PT_LOOS + 0x14,
00473 };
00474
00476 enum ELF_PFs
00477 {
00478     PF_X              = 0x1,
00479     PF_W              = 0x2,
00480     PF_R              = 0x4,
00481     PF_MASKOS         = 0x0ff00000,
00482     PF_MASKPROC       = 0x7fffffff,
00483 };
00484
00486 enum Elf_NTs_core
00487 {
00488     NT_PRSTATUS       = 1,
00489     NT_FPREGSET       = 2,
00490     NT_PRPSINFO       = 3,
00491     NT_PRXREG         = 4,
00492     NT_TASKSTRUCT     = 4,
00493     NT_PLATFORM       = 5,
00494     NT_AUXV           = 6,
00495     NT_GWINDOWS       = 7,
00496     NT_ASRS           = 8,

```

```

00497 NT_PSTATUS           = 10,
00498 NT_PSINFO             = 13,
00499 NT_PRCREAD            = 14,
00500 NT_UTSNAME             = 15,
00501 NT_LWPSTATUS           = 16,
00502 NT_LWPSINFO           = 17,
00503 NT_PRFPXREG           = 20,
00504 };
00505
00507 enum Elf_NTs_obj
00508 {
00509     NT_VERSION           = 1,
00510 };
00511
00513 typedef struct
00514 {
00515     Elf32_Sword   d_tag;
00516     union
00517     {
00518         Elf32_Word d_val;
00519         Elf32_Addr d_ptr;
00520     } d_un;
00521 } Elf32_Dyn;
00522
00524 typedef struct
00525 {
00526     Elf64_Sxword d_tag;
00527     union
00528     {
00529         Elf64_Xword d_val;
00530         Elf64_Addr d_ptr;
00531     } d_un;
00532 } Elf64_Dyn;
00533
00535 enum Elf_DTs
00536 {
00537     DT_NULL           = 0,
00538     DT_NEEDED         = 1,
00539     DT_PLTRELSZ       = 2,
00540     DT_PLTGOT         = 3,
00541     DT_HASH           = 4,
00542     DT_STRTAB         = 5,
00543     DT_SYMTAB         = 6,
00544     DT_RELA           = 7,
00545     DT_RELASZ         = 8,
00546     DT_RELAENT        = 9,
00547     DT_STRSZ          = 10,
00548     DT_SYMENT         = 11,
00549     DT_INIT           = 12,
00550     DT_FINI           = 13,
00551     DT_SONAME         = 14,
00552     DT_RPATH          = 15,
00553     DT_SYMBOLIC       = 16,
00554     DT_REL            = 17,
00555     DT_RELSZ          = 18,
00556     DT_RELENT         = 19,
00557     DT_PTRREL         = 20,
00558     DT_DEBUG          = 21,
00559     DT_TEXTREL        = 22,
00560     DT_JMPREL         = 23,
00561     DT_BIND_NOW       = 24,
00562     DT_INIT_ARRAY     = 25,
00563     DT_FINI_ARRAY     = 26,
00564     DT_INIT_ARRAYSZ   = 27,
00565     DT_FINI_ARRAYSZ   = 28,
00566     DT_RUNPATH        = 29,
00567     DT_FLAGS          = 30,
00568     DT_ENCODING       = 32,
00569     DT_PREINIT_ARRAY  = 32,
00570     DT_PREINIT_ARRAYSZ = 33,
00571     DT_NUM            = 34,
00572     DT_LOOS           = 0x6000000d,
00573     DT_HIOS           = 0x6ffff000,
00574     DT_LOPROC         = 0x70000000,
00575     DT_HIPROC         = 0x7fffffff,
00576 };
00577
00581 enum Elf_DFs
00582 {
00583     DF_ORIGIN         = 0x00000001,
00584     DF_SYMBOLIC       = 0x00000002,
00585     DF_TEXTREL        = 0x00000004,
00586     DF_BIND_NOW       = 0x00000008,
00587     DF_STATIC_TLS     = 0x00000010,
00588 };
00589
00594 enum Elf_DF_1s

```

```

00595 {
00596     DF_1_NOW                = 0x00000001,
00597     DF_1_GLOBAL             = 0x00000002,
00598     DF_1_GROUP              = 0x00000004,
00599     DF_1_NODELETE           = 0x00000008,
00600     DF_1_LOADFLTR          = 0x00000010,
00601     DF_1_INITFIRST         = 0x00000020,
00602     DF_1_NOOPEN             = 0x00000040,
00603     DF_1_ORIGIN            = 0x00000080,
00604     DF_1_DIRECT            = 0x00000100,
00605     DF_1_TRANS              = 0x00000200,
00606     DF_1_INTERPOSE          = 0x00000400,
00607     DF_1_NODEFLIB          = 0x00000800,
00608     DF_1_NODUMP            = 0x00001000,
00609     DF_1_CONFALT           = 0x00002000,
00610     DF_1_ENDFILTEE         = 0x00004000,
00611     DF_1_DISPRELDNE        = 0x00008000,
00612     DF_1_DISPRELPND        = 0x00010000,
00613 };
00614
00616 enum Elf_DTF_1s
00617 {
00618     DTF_1_PARINIT           = 0x00000001,
00619     DTF_1_CONFEXP          = 0x00000002,
00620 };
00621
00623 enum Elf_DF_P1s
00624 {
00625     DF_P1_LAZYLOAD          = 0x00000001,
00626     DF_P1_GROUPPERM        = 0x00000002,
00627 };
00628
00629
00631 typedef struct
00632 {
00633     Elf32_Addr              r_offset;
00634     Elf32_Word              r_info;
00635 } Elf32_Rel;
00636
00638 typedef struct
00639 {
00640     Elf32_Addr              r_offset;
00641     Elf32_Word              r_info;
00642     Elf32_Sword             r_addend;
00643 } Elf32_Rela;
00644
00646 typedef struct
00647 {
00648     Elf64_Addr              r_offset;
00649     Elf64_Xword             r_info;
00650 } Elf64_Rel;
00651
00653 typedef struct
00654 {
00655     Elf64_Addr              r_offset;
00656     Elf64_Xword             r_info;
00657     Elf64_Sxword            r_addend;
00658 } Elf64_Rela;
00659
00661 #define ELF32_R_SYM(i)      ((i)>>8)
00663 #define ELF32_R_TYPE(i)    ((unsigned char)(i))
00665 #define ELF32_R_INFO(s,t)  (((s)<<8)+(unsigned char)(t))
00666
00668 #define ELF64_R_SYM(i)      ((i)>>32)
00669
00671 #define ELF64_R_TYPE(i)    ((i)&0xffffffffL)
00672
00674 #define ELF64_R_INFO(s,t)  (((s)<<32)+(t)&0xffffffffL)
00675
00677 enum Elf_R_386_s
00678 {
00679     R_386_NONE              = 0,
00680     R_386_32                = 1,
00681     R_386_PC32              = 2,
00682     R_386_GOT32             = 3,
00683     R_386_PLT32             = 4,
00684     R_386_COPY              = 5,
00685     R_386_GLOB_DAT          = 6,
00686     R_386_JMP_SLOT          = 7,
00687     R_386_RELATIVE          = 8,
00688     R_386_GOTOFF            = 9,
00689     R_386_GOTPC             = 10,
00690     R_386_32PLT             = 11,
00691     R_386_TLS_TPOFF         = 14,
00692     R_386_TLS_IE            = 15,
00694     R_386_TLS_GOTIE         = 16,
00695     R_386_TLS_LE            = 17,
00696     R_386_TLS_GD            = 18,

```

```

00698 R_386_TLS_LDM          = 19,
00700 R_386_16                = 20,
00701 R_386_PC16            = 21,
00702 R_386_8                = 22,
00703 R_386_PC8              = 23,
00704 R_386_TLS_GD_32       = 24,
00706 R_386_TLS_GD_PUSH     = 25,
00707 R_386_TLS_GD_CALL      = 26,
00709 R_386_TLS_GD_POP     = 27,
00710 R_386_TLS_LDM_32       = 28,
00712 R_386_TLS_LDM_PUSH    = 29,
00713 R_386_TLS_LDM_CALL    = 30,
00715 R_386_TLS_LDM_POP     = 31,
00716 R_386_TLS_LDO_32      = 32,
00717 R_386_TLS_LE_32       = 33,
00719 R_386_TLS_LE_32      = 34,
00721 R_386_TLS_DTPOMOD32   = 35,
00722 R_386_TLS_DTPOFF32    = 36,
00723 R_386_TLS_TPOFF32     = 37,
00724 R_386_NUM              = 38,
00725 };
00726
00728
00730 enum Elf_EF_ARM_s
00731 {
00732     EF_ARM_RELEXEC          = 0x01,
00733     EF_ARM_HASENTRY         = 0x02,
00734     EF_ARM_INTERWORK        = 0x04,
00735     EF_ARM_APCS_26          = 0x08,
00736     EF_ARM_APCS_FLOAT       = 0x10,
00737     EF_ARM_PIC              = 0x20,
00738     EF_ARM_ALIGN8           = 0x40,
00739     EF_ARM_NEW_ABI          = 0x80,
00740     EF_ARM_OLD_ABI          = 0x100,
00741
00742     /* Other constants defined in the ARM ELF spec. version B-01. */
00743     /* NB. These conflict with values defined above. */
00744     EF_ARM_SYMSARESORTED    = 0x04,
00745     EF_ARM_DYNSYMSUSESEGIDX = 0x08,
00746     EF_ARM_MAPSYMSFIRST     = 0x10,
00747     EF_ARM_EABIMASK         = 0xFF000000,
00748
00749     #define EF_ARM_EABI_VERSION(flags) ((flags) & EF_ARM_EABIMASK)
00750     EF_ARM_EABI_UNKNOWN     = 0x00000000,
00751     EF_ARM_EABI_VER1        = 0x01000000,
00752     EF_ARM_EABI_VER2        = 0x02000000,
00753 };
00754
00756 enum Elf_STT_ARM_s
00757 {
00758     STT_ARM_TFUNC           = 0xd,
00759 };
00760
00762 enum Elf_SHF_s_ARM
00763 {
00764     SHF_ARM_ENTRYSECT       = 0x10000000,
00765     SHF_ARM_COMDEF          = 0x80000000,
00766 };
00768
00770 enum Elf_ARM_SBs
00771 {
00772     PF_ARM_SB               = 0x10000000,
00773 };
00775
00777 enum Elf_R_ARM_s
00778 {
00779     R_ARM_NONE              = 0,
00780     R_ARM_PC24              = 1,
00781     R_ARM_ABS32             = 2,
00782     R_ARM_REL32             = 3,
00783     R_ARM_PC13              = 4,
00784     R_ARM_ABS16             = 5,
00785     R_ARM_ABS12             = 6,
00786     R_ARM_THM_ABS5          = 7,
00787     R_ARM_ABS8              = 8,
00788     R_ARM_SBREL32           = 9,
00789     R_ARM_THM_PC22          = 10,
00790     R_ARM_THM_PC8           = 11,
00791     R_ARM_AMP_VCALL9        = 12,
00792     R_ARM_SWI24             = 13,
00793     R_ARM_THM_SWI8          = 14,
00794     R_ARM_XPC25             = 15,
00795     R_ARM_THM_XPC22         = 16,
00796     R_ARM_COPY              = 20,
00797     R_ARM_GLOB_DAT          = 21,
00798     R_ARM_JUMP_SLOT         = 22,
00799     R_ARM_RELATIVE          = 23,

```

```

00800 R_ARM_GOTOFF          = 24,
00801 R_ARM_GOTPC           = 25,
00802 R_ARM_GOT32          = 26,
00803 R_ARM_PLT32          = 27,
00804 R_ARM_ALU_PCREL_7_0  = 32,
00805 R_ARM_ALU_PCREL_15_8 = 33,
00806 R_ARM_ALU_PCREL_23_15 = 34,
00807 R_ARM_LDR_SBREL_11_0 = 35,
00808 R_ARM_ALU_SBREL_19_12 = 36,
00809 R_ARM_ALU_SBREL_27_20 = 37,
00810 R_ARM_GNU_VTENTRY    = 100,
00811 R_ARM_GNU_VTINHERIT = 101,
00812 R_ARM_THM_PC11       = 102,
00813 R_ARM_THM_PC9         = 103,
00814 R_ARM_RXPC25         = 249,
00815 R_ARM_RSBREL32       = 250,
00816 R_ARM_THM_RPC22      = 251,
00817 R_ARM_RREL32        = 252,
00818 R_ARM_RABS22        = 253,
00819 R_ARM_RPC24         = 254,
00820 R_ARM_RBASE         = 255,
00821 R_ARM_NUM           = 256,
00822 };
00823
00825 enum Elf_R_AARCH64_s
00826 {
00827     R_AARCH64_NONE          = 0,
00828     R_AARCH64_RELATIVE     = 1027,
00829 };
00830
00832 enum Elf_R_X86_64_s
00833 {
00834     R_X86_64_NONE          = 0,
00835     R_X86_64_64           = 1,
00836     R_X86_64_PC32         = 2,
00837     R_X86_64_GOT32        = 3,
00838     R_X86_64_PLT32        = 4,
00839     R_X86_64_COPY         = 5,
00840     R_X86_64_GLOB_DAT     = 6,
00841     R_X86_64_JUMP_SLOT    = 7,
00842     R_X86_64_RELATIVE     = 8,
00843     R_X86_64_GOTPCREL     = 9,
00844     R_X86_64_32          = 10,
00845     R_X86_64_32S         = 11,
00846     R_X86_64_16          = 12,
00847     R_X86_64_PC16        = 13,
00848     R_X86_64_8           = 14,
00849     R_X86_64_PC8         = 15,
00850     R_X86_64_DTPMOD64     = 16,
00851     R_X86_64_DTPOFF64    = 17,
00852     R_X86_64_TPOFF64     = 18,
00853     R_X86_64_TLSGD       = 19,
00855     R_X86_64_TLSLD       = 20,
00857     R_X86_64_DTPOFF32    = 21,
00858     R_X86_64_GOTTPOFF    = 22,
00860     R_X86_64_TPOFF32     = 23,
00861     R_X86_64_NUM         = 24,
00862 };
00863
00865 enum Elf_STNs
00866 {
00867     STN_UNDEF              = 0,
00868 };
00869
00871 typedef struct
00872 {
00873     Elf32_Word             st_name;
00874     Elf32_Addr             st_value;
00875     Elf32_Word             st_size;
00876     unsigned char          st_info;
00877     unsigned char          st_other;
00878     Elf32_Half             st_shndx;
00879 } Elf32_Sym;
00880
00882 typedef struct
00883 {
00884     Elf64_Word             st_name;
00885     unsigned char          st_info;
00886     unsigned char          st_other;
00887     Elf64_Half             st_shndx;
00888     Elf64_Addr             st_value;
00889     Elf64_Xword            st_size;
00890 } Elf64_Sym;
00891
00893 #define ELF32_ST_BIND(i)    ((i)>4)
00894
00896 #define ELF32_ST_TYPE(i)    ((i)&0xf)

```

```

00897
00899 #define ELF32_ST_INFO(b,t)  (((b) << 4) + ((t) & 0xf))
00900
00902 #define ELF64_ST_BIND(i)    ((i) >> 4)
00903
00905 #define ELF64_ST_TYPE(i)    ((i) & 0xf)
00906
00908 #define ELF64_ST_INFO(b,t)  (((b) << 4) + ((t) & 0xf))
00909
00912 enum Elf_STBs
00913 {
00914     STB_LOCAL    = 0,
00915     STB_GLOBAL   = 1,
00916     STB_WEAK     = 2,
00917     STB_LOOS     = 10,
00918     STB_HIOS     = 12,
00919     STB_LOPROC   = 13,
00920     STB_HIPROC   = 15,
00921 };
00922
00925 enum Elf_STTs
00926 {
00927     STT_NOTYPE    = 0,
00928     STT_OBJECT    = 1,
00929     STT_FUNC      = 2,
00930     STT_SECTION   = 3,
00931     STT_FILE      = 4,
00932     STT_LOOS      = 10,
00933     STT_HIOS      = 12,
00934     STT_LOPROC    = 13,
00935     STT_HIPROC    = 15,
00936 };
00937
00939 enum Elf_ATs
00940 {
00941     AT_NULL        = 0,
00942     AT_IGNORE      = 1,
00943     AT_EXECD      = 2,
00944     AT_PHDR        = 3,
00945     AT_PHENT       = 4,
00946     AT_PHNUM       = 5,
00947     AT_PAGESZ      = 6,
00948     AT_BASE        = 7,
00949     AT_FLAGS       = 8,
00950     AT_ENTRY       = 9,
00951     AT_NOTELF      = 10,
00952     AT_UID         = 11,
00953     AT_EUID        = 12,
00954     AT_GID         = 13,
00955     AT_EGID        = 14,
00956
00957     AT_L4_AUX       = 0xf0,
00958     AT_L4_ENV       = 0xf1,
00959     AT_L4_KIP       = 0xf2,
00960 };
00961
00963 typedef struct Elf32_Auxv
00964 {
00965     Elf32_Word atype;
00966     Elf32_Word avalue;
00967 } Elf32_Auxv;
00968
00970 typedef struct Elf64_Auxv
00971 {
00972     Elf64_Word atype;
00973     Elf64_Word avalue;
00974 } Elf64_Auxv;
00975
00976 typedef struct
00977 {
00978     Elf32_Word n_namesz;
00979     Elf32_Word n_descsz;
00980     Elf32_Word n_type;
00981 } Elf32_Nhdr;
00982
00983 typedef struct
00984 {
00985     Elf64_Word n_namesz;
00986     Elf64_Word n_descsz;
00987     Elf64_Word n_type;
00988 } Elf64_Nhdr;
00989
00997 static inline int l4util_elf_check_magic(ElfW(Ehdr) const *hdr);
00998
01006 static inline int l4util_elf_check_arch(ElfW(Ehdr) const *hdr);
01007
01014 static inline ElfW(Phdr) *l4util_elf_phdr(ElfW(Ehdr) const *hdr);

```



```

01015
01016
01017 /* Implementations */
01018
01019 static inline
01020 int l4util_elf_check_magic(ElfW(Ehdr) const *hdr)
01021 {
01022     return    hdr->e_ident[EI_MAG0] == ELFMAG0
01023             && hdr->e_ident[EI_MAG1] == ELFMAG1
01024             && hdr->e_ident[EI_MAG2] == ELFMAG2
01025             && hdr->e_ident[EI_MAG3] == ELFMAG3;
01026 }
01027
01028 static inline
01029 int l4util_elf_check_arch(ElfW(Ehdr) const *hdr)
01030 {
01031     return    hdr->e_ident[EI_CLASS] == L4_ARCH_EI_CLASS
01032             && hdr->e_ident[EI_DATA]  == L4_ARCH_EI_DATA
01033             && hdr->e_machine        == L4_ARCH_E_MACHINE;
01034 }
01035
01036 static inline
01037 ElfW(Phdr) *l4util_elf_phdr(ElfW(Ehdr) const *hdr)
01038 {
01039     return (ElfW(Phdr) *) ((char *)hdr + hdr->e_phoff);
01040 }


```

## 16.634 l4/util/getopt.h File Reference


getopt

```
#include <l4/sys/compiler.h>
```

Include dependency graph for getopt.h:



This graph shows which files directly or indirectly include this file:



### 16.634.1 Detailed Description

getopt

Definition in file [getopt.h](#).

## 16.635 getopt.h

[Go to the documentation of this file.](#)

```

00001
00005 /*
00006  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00007  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00008  *      economic rights: Technische Universität Dresden (Germany)
00009  * License: see LICENSE.spdx (in this directory or the directories above)
00010  */
00011 #ifndef _GETOPT_H
00012 #define _GETOPT_H
00013
00014 #ifndef NULL
00015 #define NULL 0
00016 #endif
00017
00018 #include <l4/sys/compiler.h>
00019
00020 L4_BEGIN_DECLS
00021
00022 /* For communication from `getopt' to the caller.
00023  * When `getopt' finds an option that takes an argument,
00024  * the argument value is returned here.
00025  * Also, when `ordering' is RETURN_IN_ORDER,
00026  * each non-option ARGV-element is returned here.  */
00027 extern char *optarg;
00028
00029
00030 /* Index in ARGV of the next element to be scanned.
00031  * This is used for communication to and from the caller
00032  * and for communication between successive calls to `getopt'.
00033  *
00034  * On entry to `getopt', zero means this is the first call; initialize.
00035  *
00036  * When `getopt' returns -1, this is the index of the first of the
00037  * non-option elements that the caller should itself scan.
00038  *
00039  * Otherwise, `optind' communicates from one call to the next
00040  * how much of ARGV has been scanned so far.  */
00041
00042 extern int optind;
  
```

```


00043
00044 /* Callers store zero here to inhibit the error message `getopt' prints
00045    for unrecognized options. */
00046
00047 extern int opterr;
00048
00049 /* Set to an option character which was unrecognized. */
00050
00051 extern int getopt;
00052
00053 /* Describe the long-named options requested by the application.
00054    The LONG_OPTIONS argument to getopt_long or getopt_long_only is a vector
00055    of `struct option' terminated by an element containing a name which is
00056    zero.
00057
00058    The field `has_arg' is:
00059    no_argument      (or 0) if the option does not take an argument,
00060    required_argument (or 1) if the option requires an argument,
00061    optional_argument (or 2) if the option takes an optional argument.
00062
00063    If the field `flag' is not NULL, it points to a variable that is set
00064    to the value given in the field `val' when the option is found, but
00065    left unchanged if the option is not found.
00066
00067    To have a long-named option do something other than set an `int' to
00068    a compiled-in constant, such as set a value from `optarg', set the
00069    option's `flag' field to zero and its `val' field to a nonzero
00070    value (the equivalent single-letter option character, if there is
00071    one). For long options that have a zero `flag' field, `getopt'
00072    returns the contents of the `val' field. */
00073
00074 struct option
00075 {
00076     const char *name;
00077     /* has_arg can't be an enum because some compilers complain about
00078        type mismatches in all the code that assumes it is an int. */
00079     int has_arg;
00080     int *flag;
00081     int val;
00082 };
00083
00084 /* Names for the values of the `has_arg' field of `struct option'. */
00085
00086 #define no_argument      0
00087 #define required_argument 1
00088 #define optional_argument 2
00089
00090 L4_CV int getopt (int argc, char *const *argv, const char *shortopts);
00091
00092 L4_CV int getopt_long (int argc, char *const *argv, const char *shortopts,
00093                       const struct option *longopts, int *longind);
00094 L4_CV int getopt_long_only (int argc, char *const *argv,
00095                             const char *shortopts,
00096                             const struct option *longopts, int *longind);
00097
00098 L4_CV int _getopt_internal (int argc, char *const *argv,
00099                             const char *shortopts,
00100                             const struct option *longopts, int *longind,
00101                             int long_only);
00102
00103 L4_END_DECLS
00104
00105 #endif /* _GETOPT_H */

```

## 16.636 l4/util/keymap.h File Reference

Event to ASCII key mapping.

```
#include <l4/sys/compiler.h>
Include dependency graph for keymap.h:
```



### 16.636.1 Detailed Description

Event to ASCII key mapping.

Definition in file [keymap.h](#).

## 16.637 keymap.h

[Go to the documentation of this file.](#)

```
00001
00005 /*
00006  * (c) 2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>
00007  *     economic rights: Technische Universität Dresden (Germany)
00008  * License: see LICENSE.spdx (in this directory or the directories above)
00009  */
00010 #ifndef __L4UTIL__KEYMAP_H__
00011 #define __L4UTIL__KEYMAP_H__
00012
00013 #include <l4/sys/compiler.h>
00014
00015 L4_BEGIN_DECLS
00016
00017 int l4util_map_event_to_keymap(unsigned value, unsigned shift);
00018
00019 L4_END_DECLS
00020
00021
00022 #endif /* __L4UTIL__KEYMAP_H__ */
```

## 16.638 kip.h

```
00001 /*
00002  * Copyright (C) 2026 Kernkonzept GmbH.
00003  * Author(s): Jan Klötzke <jan.kloetzke@kernkonzept.com>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007 #pragma once
```

## 16.639 kip.h

```

00001 /*
00002  * Copyright (C) 2026 Kernkonzept GmbH.
00003  * Author(s): Jan Klötzke <jan.kloetzke@kernkonzept.com>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007 #pragma once

```

## 16.640 kip.h

```

00001 /*
00002  * Copyright (C) 2026 Kernkonzept GmbH.
00003  * Author(s): Jan Klötzke <jan.kloetzke@kernkonzept.com>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007 #pragma once

```

## 16.641 l4/sys/kip.h File Reference


Kernel Info Page access functions.

```


#include <l4/sys/compiler.h>
#include <l4/sys/l4int.h>
#include <l4/sys/__kip-arch.h>
#include <l4/sys/arch/kip.h>

```

Include dependency graph for kip.h:



This graph shows which files directly or indirectly include this file:



## Data Structures

- struct [l4\\_kernel\\_info\\_t](#)  
*L4 Kernel Interface Page.*

## Macros

- #define **L4\_KERNEL\_INFO\_MAGIC** (0x4BE6344CL) /\* "L4μK" \*/  
*Kernel Info Page identifier ("L4μK").*
- #define [l4\\_kip\\_for\\_each\\_feature](#)(s)  
*Cycle through kernel features given in the KIP.*

## Typedefs

- typedef struct [l4\\_kernel\\_info\\_t](#) [l4\\_kernel\\_info\\_t](#)  
*L4 Kernel Interface Page.*

## Enumerations

- enum { [L4\\_KIP\\_OFFSET\\_READ\\_US](#) = 0x900 , [L4\\_KIP\\_OFFSET\\_READ\\_NS](#) = 0x980 }

## Functions

- [l4\\_kernel\\_info\\_t](#) const \* [l4\\_kip](#) (void) [L4\\_NOTHROW](#)  
*Get Kernel Info Page.*
- [l4\\_umword\\_t](#) [l4\\_kip\\_version](#) ([l4\\_kernel\\_info\\_t](#) const \*kip) [L4\\_NOTHROW](#)  
*Get the kernel version.*
- const char \* [l4\\_kip\\_version\\_string](#) ([l4\\_kernel\\_info\\_t](#) const \*kip) [L4\\_NOTHROW](#)  
*Get the kernel version string.*
- int [l4\\_kernel\\_info\\_version\\_offset](#) ([l4\\_kernel\\_info\\_t](#) const \*kip) [L4\\_NOTHROW](#)  
*Return offset in bytes of version\_strings relative to the KIP base.*
- [l4\\_cpu\\_time\\_t](#) [l4\\_kip\\_clock](#) ([l4\\_kernel\\_info\\_t](#) const \*kip) [L4\\_NOTHROW](#)  
*Return clock value from the KIP.*
- [l4\\_umword\\_t](#) [l4\\_kip\\_clock\\_lw](#) ([l4\\_kernel\\_info\\_t](#) const \*kip) [L4\\_NOTHROW](#)  
*Return least significant machine word of clock value from the KIP.*
- [l4\\_uint64\\_t](#) [l4\\_kip\\_clock\\_ns](#) ([l4\\_kernel\\_info\\_t](#) const \*kip) [L4\\_NOTHROW](#)  
*Return current clock using the KIP in nanoseconds.*
- int [l4\\_kip\\_kernel\\_has\\_feature](#) ([l4\\_kernel\\_info\\_t](#) const \*kip, char const \*str)  
*Check if kernel supports a feature.*

### 16.641.1 Detailed Description

Kernel Info Page access functions.

Definition in file [kip.h](#).

## 16.641.2 Macro Definition Documentation

### 16.641.2.1 l4\_kip\_for\_each\_feature

```
#define l4_kip_for_each_feature(  
    s)
```

**Value:**

```
for (s += __builtin_strlen(s) + 1; *s; s += __builtin_strlen(s) + 1)
```

Cycle through kernel features given in the KIP.

Cycles through all KIP kernel feature strings. *s* must be a character pointer (`char const *`) initialized with [l4\\_kip\\_version\\_string\(\)](#).

Definition at line 272 of file [kip.h](#).

Referenced by [l4\\_kip\\_kernel\\_has\\_feature\(\)](#).

## 16.641.3 Function Documentation

### 16.641.3.1 l4\_kip\_kernel\_has\_feature()

```
int l4_kip_kernel_has_feature (  
    l4_kernel_info_t const * kip,  
    char const * str) [inline]
```

Check if kernel supports a feature.

**Parameters**

<i>kip</i>	Pointer to the kernel info page (KIP).
<i>str</i>	Feature name to check.

**Returns**


1 if the kernel supports the feature, 0 if not.

Checks the feature field in the KIP for the given string.

Definition at line 286 of file [kip.h](#).

References [l4\\_kip\\_for\\_each\\_feature](#), and [l4\\_kip\\_version\\_string\(\)](#).

Here is the call graph for this function:



## 16.642 kip.h

[Go to the documentation of this file.](#)

```

00001
00006 /*
00007  * (c) 2008-2013 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00008  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00009  *      economic rights: Technische Universität Dresden (Germany)
00010  *
00011  * License: see LICENSE.spdx (in this directory or the directories above)
00012  */
00013 #pragma once
00014
00015 #include <l4/sys/compiler.h>
00016 #include <l4/sys/l4int.h>
00017
00018 #include <l4/sys/__kip-arch.h>
00019
00023 struct l4_kip_platform_info
00024 {
00025     char                                name[16];
00026     l4_uint32_t                        is_mp;
00027     struct l4_kip_platform_info_arch arch;
00028 };
00029
00036 typedef struct l4_kernel_info_t
00037 {
00038     /* offset 0x00 */
00039     l4_uint32_t                        magic;
00042     l4_uint32_t                        version;
00043     l4_uint8_t                        offset_version_strings;
00044     l4_uint8_t                        _fill0[3];
00045     l4_uint8_t                        kip_sys_calls;
00046     l4_uint8_t                        node;
00047     l4_uint8_t                        _fill1[2];
00048
00049     /* offset 0x10 */
00050     l4_uint64_t                        sigma0_ip;
00051     l4_uint64_t                        root_ip;
00052
00053     /* offset 0x20 */
00054     volatile l4_cpu_time_t            _clock_val;
00055     l4_uint64_t                        frequency_cpu;
00056
00057     /* offset 0x30 */
00058     l4_uint64_t                        acpi_rsdp_addr;
00059     l4_uint64_t                        dt_addr;
00060
00061     /* offset 0x40 */
00062     l4_uint64_t                        user_ptr;
00063     l4_uint64_t                        _res0[1];
00064
00065     /* offset 0x50 */
00066     l4_uint32_t                        scheduler_granularity;
00067     l4_uint32_t                        mem_descs;
00068     l4_uint32_t                        mem_descs_num;
00069     l4_uint32_t                        _res1[1];
00070
00071     /* offset 0x60 */
00072     l4_uint64_t                        _res2[2];
00073
00074     /* offset 0x70 */
00075     struct l4_kip_platform_info        platform_info;
00076 } l4_kernel_info_t;
00077
00085
00089 enum l4_kernel_info_consts_t
00090 {
00091     L4_KIP_VERSION_FIASCO              = 0x87004444,
00092     L4_KIP_VERSION_FIASCO_MASK        = 0xff00ffff,
00093 };
00094
00095 enum
00096 {
00105     L4_KIP_OFFS_READ_US                = 0x900,
00106
00116     L4_KIP_OFFS_READ_NS                = 0x980,
00117 };
00118
00122 extern l4_kernel_info_t const *l4_global_kip;
00123
00127 #define L4_KERNEL_INFO_MAGIC (0x4BE6344CL) /* "L4µK" */
00128
00129
00135 L4_INLINE l4_kernel_info_t const *l4_kip(void) L4_NOTHROW;

```




```

00136
00137
00145 L4_INLINE l4_umword_t l4_kip_version(l4_kernel_info_t const *kip) L4_NOTHROW;
00146
00154 L4_INLINE const char *l4_kip_version_string(l4_kernel_info_t const *kip) L4_NOTHROW;
00155
00164 L4_INLINE int
00165 l4_kernel_info_version_offset(l4_kernel_info_t const *kip) L4_NOTHROW;
00166
00184 L4_INLINE l4_cpu_time_t
00185 l4_kip_clock(l4_kernel_info_t const *kip) L4_NOTHROW;
00186
00199 L4_INLINE l4_umword_t
00200 l4_kip_clock_lw(l4_kernel_info_t const *kip) L4_NOTHROW
00201 L4_DEPRECATED("Use l4_kip_clock() instead");
00202
00216 L4_INLINE l4_uint64_t
00217 l4_kip_clock_ns(l4_kernel_info_t const *kip) L4_NOTHROW;
00218
00220
00221 /*****
00222  * Implementations
00223  *****/
00224
00225 L4_INLINE l4_kernel_info_t const*
00226 l4_kip(void) L4_NOTHROW
00227 { return l4_global_kip; }
00228
00229 L4_INLINE l4_umword_t
00230 l4_kip_version(l4_kernel_info_t const *kip) L4_NOTHROW
00231 { return kip->version & L4_KIP_VERSION_FIASCO_MASK; }
00232
00233 L4_INLINE const char*
00234 l4_kip_version_string(l4_kernel_info_t const *k) L4_NOTHROW
00235 { return (const char *)k + l4_kernel_info_version_offset(k); }
00236
00237 L4_INLINE int
00238 l4_kernel_info_version_offset(l4_kernel_info_t const *kip) L4_NOTHROW
00239 { return kip->offset_version_strings « 4; }
00240
00241 L4_INLINE l4_cpu_time_t
00242 l4_kip_clock(l4_kernel_info_t const *kip) L4_NOTHROW
00243 {
00244     // Use kernel-provided code to determine the current clock.
00245     typedef l4_uint64_t (*kip_time_fn_read_us)(void);
00246     kip_time_fn_read_us read_us =
00247         (kip_time_fn_read_us)((l4_uint8_t const*)kip + L4_KIP_OFFS_READ_US);
00248     return read_us();
00249 }
00250
00251 L4_INLINE l4_cpu_time_t
00252 l4_kip_clock_ns(l4_kernel_info_t const *kip) L4_NOTHROW
00253 {
00254     typedef l4_uint64_t (*kip_time_fn_read_ns)(void);
00255     kip_time_fn_read_ns read_ns =
00256         (kip_time_fn_read_ns)((l4_uint8_t const*)kip + L4_KIP_OFFS_READ_NS);
00257     return read_ns();
00258 }
00259
00260 L4_INLINE l4_umword_t
00261 l4_kip_clock_lw(l4_kernel_info_t const *kip) L4_NOTHROW
00262 {
00263     return l4_kip_clock(kip);
00264 }
00265
00272 #define l4_kip_for_each_feature(s) \
00273     for (s += __builtin_strlen(s) + 1; *s; s += __builtin_strlen(s) + 1)
00274
00285 L4_INLINE int
00286 l4_kip_kernel_has_feature(l4_kernel_info_t const *kip, char const *str)
00287 {
00288     const char *s = l4_kip_version_string(kip);
00289     if (!s)
00290         return 0;
00291     l4_kip_for_each_feature(s)
00292     {
00293         if (__builtin_strcmp(s, str) == 0)
00294             return 1;
00295     }
00296     return 0;
00297 }
00298
00299 }
00300
00301 #include <l4/sys/arch/kip.h>

```

## 16.643 l4/util/kip.h File Reference

```
#include <l4/sys/kip.h>
#include <l4/sys/compiler.h>
Include dependency graph for kip.h:
```



### Macros

- `#define l4util_kip_for_each_feature(s)`  
Cycle through kernel features given in the KIP.

### Functions

- `L4_BEGIN_DECLS int l4util_kip_kernel_has_feature (l4_kernel_info_t const *k, char const *str)`  
Check if kernel supports a feature.
- `unsigned long l4util_kip_kernel_abi_version (l4_kernel_info_t const *k)`  
Return kernel ABI version.

## 16.644 kip.h

[Go to the documentation of this file.](#)

```

00001
00005 /*
00006  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00007  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00008  *      economic rights: Technische Universität Dresden (Germany)
00009  * License: see LICENSE.spdx (in this directory or the directories above)
00010  */
00011
00012 #pragma once
00013
00014 #include <l4/sys/kip.h>
00015 #include <l4/sys/compiler.h>
00016
00022
00023
00024 L4_BEGIN_DECLS
00025
00038 L4_CV int l4util_kip_kernel_has_feature(l4_kernel_info_t const *k, char const *str);
00039
00046 L4_CV unsigned long l4util_kip_kernel_abi_version(l4_kernel_info_t const *k);
00047
00048 L4_END_DECLS
00049
00058 #define l4util_kip_for_each_feature(s) l4_kip_for_each_feature(s)
00059
00061
```


## 16.645 kip.h

```
00001 /*
00002  * Copyright (C) 2026 Kernkonzept GmbH.
00003  * Author(s): Jan Klötzke <jan.kloetzke@kernkonzept.com>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007 #pragma once
```

## 16.646 l4/util/kprintf.h File Reference

printf using the kernel debugger

```
#include <l4/sys/compiler.h>
Include dependency graph for kprintf.h:
```



### 16.646.1 Detailed Description

printf using the kernel debugger

#### Date

04/05/2007

#### Author

Adam Lackorzynski [adam@os.inf.tu-dresden.de](mailto:adam@os.inf.tu-dresden.de),

Definition in file [kprintf.h](#).

## 16.647 kprintf.h

[Go to the documentation of this file.](#)

```

00001 /*****
00009 */
00010 * (c) 2007-2009 Author(s)
00011 *     economic rights: Technische Universität Dresden (Germany)
00012 * License: see LICENSE.spdx (in this directory or the directories above)
00013 */
00014
00015 #ifndef __L4UTIL__INCLUDE__KPRINTF_H__
00016 #define __L4UTIL__INCLUDE__KPRINTF_H__
00017
00018 #include <l4/sys/compiler.h>
00019
00020 L4_BEGIN_DECLS
00021
00022 L4_CV int l4_kprintf(const char *fmt, ...)
00023                 __attribute__((format (printf, 1, 2)));
00024
00025 L4_END_DECLS
00026
00027 #endif /* ! __L4UTIL__INCLUDE__KPRINTF_H__ */


```

## 16.648 l4/util/l4mod.h File Reference

L4mod structures and constants.

```
#include <l4/sys/l4int.h>
```

Include dependency graph for l4mod.h:



### Data Structures

- struct [l4util\\_l4mod\\_mod](#)  
A single module.
- struct [l4util\\_l4mod\\_info](#)  
Base module structure.

## Enumerations

- enum `l4util_l4mod_mod_info_flag` {  
`L4util_l4mod_mod_flag_unspec` = 0 , `L4util_l4mod_mod_flag_kernel` = 1 , `L4util_l4mod_mod_flag_sigma0` =  
2 , `L4util_l4mod_mod_flag_roottask` = 3 ,  
`L4util_l4mod_mod_flag_mask` = 7 << 0 }

Flags for `l4util_l4mod_mod.flags`.

### 16.648.1 Detailed Description

L4mod structures and constants.

Definition in file `l4mod.h`.

### 16.648.2 Enumeration Type Documentation

#### 16.648.2.1 l4util\_l4mod\_mod\_info\_flag

enum `l4util_l4mod_mod_info_flag`

Flags for `l4util_l4mod_mod.flags`.

#### Enumerator

<code>L4util_l4mod_mod_flag_unspec</code>	Flag for a generic module.
<code>L4util_l4mod_mod_flag_kernel</code>	Flag for the kernel module.
<code>L4util_l4mod_mod_flag_sigma0</code>	Flag for the sigma0 module.
<code>L4util_l4mod_mod_flag_roottask</code>	Flag for the root task module.
<code>L4util_l4mod_mod_flag_mask</code>	Mask for specified flags.

Definition at line 17 of file `l4mod.h`.

## 16.649 l4mod.h

[Go to the documentation of this file.](#)

```

00001 /*
00002  * Copyright (C) 2021-2022, 2024 Kernkonzept GmbH.
00003  * Author(s): Adam Lackorzynski <adam@l4re.org>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007
00012 #pragma once
00013
00014 #include <l4/sys/l4int.h>
00015
00017 enum l4util_l4mod_mod_info_flag
00018 {
00019     L4util_l4mod_mod_flag_unspec    = 0,
00020     L4util_l4mod_mod_flag_kernel    = 1,
00021     L4util_l4mod_mod_flag_sigma0    = 2,
00022     L4util_l4mod_mod_flag_roottask  = 3,
00023     L4util_l4mod_mod_flag_mask      = 7 << 0,
00024 };

```

```

00025
00027 typedef struct
00028 {
00029     l4_uint64_t flags;
00030     l4_uint64_t mod_start;
00031     l4_uint64_t mod_end;
00032     l4_uint64_t cmdline;
00033 } l4util_l4mod_mod;
00034
00036 typedef struct
00037 {
00038     l4_uint64_t flags;
00039     l4_uint64_t cmdline;
00040     l4_uint64_t mods_addr;
00041     l4_uint32_t mods_count;
00042     l4_uint32_t _pad;
00043
00048     l4_uint64_t vbe_ctrl_info;
00049     l4_uint64_t vbe_mode_info;
00050 } l4util_l4mod_info;

```


## 16.650 l4/util/list\_alloc.h File Reference

Simple list-based allocator.

```

#include <l4/sys/l4int.h>
#include <l4/sys/compiler.h>
Include dependency graph for list_alloc.h:

```



### Functions

- `L4_BEGIN_DECLS` void `l4la_free` (`l4la_free_t **first`, void `*block`, `l4_size_t` `size`)  
*Add free memory to memory pool.*
- void `* l4la_alloc` (`l4la_free_t **first`, `l4_size_t` `size`, unsigned `align`)  
*Allocate memory from pool.*
- void `l4la_dump` (`l4la_free_t **first`)  
*Show all list members.*
- void `l4la_init` (`l4la_free_t **first`)  
*Init memory pool.*
- `l4_size_t` `l4la_avail` (`l4la_free_t **first`)  
*Show available memory in pool.*

## 16.650.1 Detailed Description

Simple list-based allocator.

Taken from the Fiasco kernel.

Date

Alexander Warg <aw11os.inf.tu-dresden.de> Frank Mehnert [fm3@os.inf.tu-dresden.de](mailto:fm3@os.inf.tu-dresden.de)

Definition in file [list\\_alloc.h](#).

## 16.650.2 Function Documentation

### 16.650.2.1 l4la\_alloc()

```
void * l4la_alloc (  
    l4la_free_t ** first,  
    l4_size_t size,  
    unsigned align)
```

Allocate memory from pool.

#### Parameters

<i>first</i>	list identifier
<i>size</i>	length of memory block to allocate
<i>align</i>	alignment

References [L4\\_CV](#).

### 16.650.2.2 l4la\_avail()

```
l4_size_t l4la_avail (  
    l4la_free_t ** first)
```

Show available memory in pool.

#### Parameters

<i>first</i>	list identifier
--------------	-----------------

References [L4\\_CV](#), and [L4\\_END\\_DECLS](#).

### 16.650.2.3 l4la\_dump()

```
void l4la_dump (  
    l4la_free_t ** first)
```

Show all list members.

#### Parameters

<i>first</i>	list identifier
--------------	-----------------

References [L4\\_CV](#).

### 16.650.2.4 l4la\_free()

```
L4_BEGIN_DECLS void l4la_free (  
    l4la_free_t ** first,  
    void * block,  
    l4_size_t size)
```

Add free memory to memory pool.

#### Parameters

<i>first</i>	list identifier
<i>block</i>	address of unused memory block
<i>size</i>	size of memory block

References [L4\\_CV](#).

### 16.650.2.5 l4la\_init()

```
void l4la_init (  
    l4la_free_t ** first)
```

Init memory pool.

#### Parameters

<i>first</i>	list identifier
--------------	-----------------

References [L4\\_CV](#).



## 16.651 list\_alloc.h

[Go to the documentation of this file.](#)


```
00001
00007
00008 /*
00009  * (c) 2003-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00010  *      Frank Mehnert <fm3@os.inf.tu-dresden.de>
00011  *      economic rights: Technische Universität Dresden (Germany)
00012  * License: see LICENSE.spdx (in this directory or the directories above)
00013  */
00014
00015 #ifndef L4UTIL_L4LA_H
00016 #define L4UTIL_L4LA_H
00017
00018 #include <l4/sys/l4int.h>
00019 #include <l4/sys/compiler.h>
00020
00021 typedef struct l4la_free_t_s
00022 {
00023     struct l4la_free_t_s *next;
00024     l4_size_t             size;
00025 } l4la_free_t;
00026
00027 #define L4LA_INITIALIZER { 0 }
00028
00029 L4_BEGIN_DECLS
00030
00035 L4_CV void      l4la_free(l4la_free_t **first, void *block, l4_size_t size);
00036
00041 L4_CV void*     l4la_alloc(l4la_free_t **first, l4_size_t size, unsigned align);
00042
00045 L4_CV void      l4la_dump(l4la_free_t **first);
00046
00049 L4_CV void      l4la_init(l4la_free_t **first);
00050
00053 L4_CV l4_size_t l4la_avail(l4la_free_t **first);
00054
00055 L4_END_DECLS
00056
00057 #endif
```

## 16.652 l4/util/lock.h File Reference

Simple lock implementation.

```
#include <l4/sys/thread.h>
#include <l4/sys/compiler.h>
#include <l4/util/atomic.h>
```

Include dependency graph for lock.h:



## 16.652.1 Detailed Description

Simple lock implementation.

Does only work if all thread have the same priority!

Date

02/1997

Author

Michael Hohmuth [hohmuth@os.inf.tu-dresden.de](mailto:hohmuth@os.inf.tu-dresden.de)

Definition in file [lock.h](#).

## 16.653 lock.h

[Go to the documentation of this file.](#)

```

00001 /*****
00009 */
00010 * (c) 2000-2009 Author(s)
00011 *     economic rights: Technische Universität Dresden (Germany)
00012 * License: see LICENSE.spdx (in this directory or the directories above)
00013 */
00014
00015 /*****
00016 #ifndef __L4UTIL_LOCK_H__
00017 #define __L4UTIL_LOCK_H__
00018
00019 #include <l4/sys/thread.h>
00020 #include <l4/sys/compiler.h>
00021 #include <l4/util/atomic.h>

```

```

00022
00023 L4_BEGIN_DECLS
00024
00025 typedef l4_uint32_t l4util_simple_lock_t;
00026
00027 L4_INLINE int l4_simple_try_lock(l4util_simple_lock_t *lock);
00028 L4_INLINE void l4_simple_unlock(l4util_simple_lock_t *lock);
00029 L4_INLINE int l4_simple_lock_locked(l4util_simple_lock_t *lock);
00030 L4_INLINE void l4_simple_lock_solid(register l4util_simple_lock_t *p);
00031 L4_INLINE void l4_simple_lock(l4util_simple_lock_t * lock);
00032
00033 L4_INLINE int
00034 l4_simple_try_lock(l4util_simple_lock_t *lock)
00035 {
00036     return l4util_xchg32(lock, 1) == 0;
00037 }
00038
00039 L4_INLINE void
00040 l4_simple_unlock(l4util_simple_lock_t *lock)
00041 {
00042     *lock = 0;
00043 }
00044
00045 L4_INLINE int
00046 l4_simple_lock_locked(l4util_simple_lock_t *lock)
00047 {
00048     return (*lock == 0) ? 0 : 1;
00049 }
00050
00051 L4_INLINE void
00052 l4_simple_lock_solid(register l4util_simple_lock_t *p)
00053 {
00054     while (l4_simple_lock_locked(p) || !l4_simple_try_lock(p))
00055         l4_thread_switch(L4_INVALID_CAP);
00056 }
00057
00058 L4_INLINE void
00059 l4_simple_lock(l4util_simple_lock_t * lock)
00060 {
00061     if (!l4_simple_try_lock(lock))
00062         l4_simple_lock_solid(lock);
00063 }
00064
00065 L4_END_DECLS
00066
00067 #endif

```

## 16.654 l4/util/mb\_info.h File Reference


Multiboot info structure as defined by GRUB.

```


#include <l4/sys/compiler.h>
#include <l4/sys/l4int.h>

```

Include dependency graph for mb\_info.h:



This graph shows which files directly or indirectly include this file:



## Data Structures

- struct [l4util\\_mb\\_mod\\_t](#)  
The structure type "mod\_list" is used by the [multiboot\\_info](#) structure.
- struct [l4util\\_mb\\_addr\\_range\\_t](#)  
*INT-15, AX=E820 style "AddressRangeDescriptor" ...with a "size" parameter on the front which is the structure size - 4, pointing to the next one, up until the full buffer length of the memory map has been reached.*
- struct [l4util\\_mb\\_drive\\_t](#)  
*Drive Info structure.*
- struct [l4util\\_mb\\_apm\\_t](#)  
*APM BIOS info.*
- struct [l4util\\_mb\\_vbe\\_ctrl\\_t](#)

- *VBE controller information.*
- struct [l4util\\_mb\\_vbe\\_mode\\_t](#)
- *VBE mode information.*
- struct [l4util\\_mb\\_info\\_t](#)
- *MultiBoot Info description.*

## Macros

- #define **MB\_ARD\_MEMORY** 1  
*usable memory "Type", all others are reserved.*
- #define **MB\_ART\_MEMORY** 1  
*Address Range Types (ART) from "Advanced Configuration and Power Interface Specification" Rev3.0a (p.*
- #define **MB\_ART\_RESERVED** 2  
*in use or reserved by system*
- #define **MB\_ART\_ACPI** 3  
*ACPI Reclaim Memory (RAM that contains ACPI tables).*
- #define **MB\_ART\_NVS** 4  
*ACPI NVS Memory (must not be used by the OS.*
- #define **MB\_ART\_UNUSABLE** 5  
*memory in which errors have been detected*
- #define [l4util\\_mb\\_for\\_each\\_mmap\\_entry](#)(i, mbi)  
*Iterate over a memory map provided in a Multiboot info.*
- #define **L4UTIL\_MB\_MEMORY** 0x00000001  
*Flags to be set in the 'flags' parameter above.*
- #define **L4UTIL\_MB\_BOOTDEV** 0x00000002  
*is there a boot device set?*
- #define **L4UTIL\_MB\_CMDLINE** 0x00000004  
*is the command-line defined?*
- #define **L4UTIL\_MB\_MODS** 0x00000008  
*are there modules to do something with?*
- #define **L4UTIL\_MB\_AOUT\_SYMS** 0x00000010  
*is there a symbol table loaded?*
- #define **L4UTIL\_MB\_ELF\_SHDR** 0x00000020  
*is there an ELF section header table?*
- #define **L4UTIL\_MB\_MEM\_MAP** 0x00000040  
*is there a full memory map?*
- #define **L4UTIL\_MB\_DRIVE\_INFO** 0x00000080  
*Is there drive info?*
- #define **L4UTIL\_MB\_CONFIG\_TABLE** 0x00000100  
*Is there a config table?*
- #define **L4UTIL\_MB\_BOOT\_LOADER\_NAME** 0x00000200  
*Is there a boot loader name?*
- #define **L4UTIL\_MB\_APM\_TABLE** 0x00000400  
*Is there a APM table?*
- #define **L4UTIL\_MB\_VIDEO\_INFO** 0x00000800  
*Is there video information?*
- #define **L4UTIL\_MB\_VALID** 0x2BADB002UL  
*If we are multiboot-compliant, this value is present in the eax register.*

### 16.654.1 Detailed Description

Multiboot info structure as defined by GRUB.

Definition in file [mb\\_info.h](#).

### 16.654.2 Macro Definition Documentation

#### 16.654.2.1 l4util\_mb\_for\_each\_mmap\_entry

```
#define l4util_mb_for_each_mmap_entry(  
    i,  
    mbi)
```

**Value:**

```
for (i = l4util_mb_first_mmap_entry(mbi);  
     (unsigned long)i < (unsigned long)mbi->mmap_addr + mbi->mmap_length;  
     i = l4util_mb_next_mmap_entry(i))
```

Iterate over a memory map provided in a Multiboot info.

#### Parameters

<i>i</i>	Name of a variable of type <a href="#">l4util_mb_addr_range_t</a> * that is consecutively assigned pointers to the entries of the memory map.
<i>mbi</i>	Pointer to the <a href="#">l4util_mb_info_t</a> where the memory map can be found.

Definition at line 332 of file [mb\\_info.h](#).

#### 16.654.2.2 L4UTIL\_MB\_MEMORY

```
#define L4UTIL_MB_MEMORY 0x00000001
```

Flags to be set in the 'flags' parameter above.

is there basic lower/upper memory information?

Definition at line 344 of file [mb\\_info.h](#).

#### 16.654.2.3 MB\_ART\_MEMORY

```
#define MB_ART_MEMORY 1
```

Address Range Types (ART) from "Advanced Configuration and Power Interface Specification" Rev3.0a (p.

390). Other values are undefined. available, usable RAM

Definition at line 64 of file [mb\\_info.h](#).

## 16.655 mb\_info.h

[Go to the documentation of this file.](#)

```

00001
00005 /*
00006  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00007  *      Frank Mehnert <fm3@os.inf.tu-dresden.de>
00008  *      economic rights: Technische Universität Dresden (Germany)
00009  * License: see LICENSE.spdx (in this directory or the directories above)
00010  */
00011
00012 #ifndef L4UTIL_MB_INFO_H
00013 #define L4UTIL_MB_INFO_H
00014
00015 /*****
00016  * Multiboot (v1)
00017  *****/
00018
00019 #ifndef __ASSEMBLY__
00020
00021 #include <l4/sys/compiler.h>
00022 #include <l4/sys/l4int.h>
00023
00024 /*
00025  * \defgroup l4util_mb_mod Multiboot v1
00026  * \ingroup l4util_api
00027  */
00028
00033 typedef struct
00034 {
00035     l4_uint32_t mod_start;
00036     l4_uint32_t mod_end;
00037     l4_uint32_t cmdline;
00038     l4_uint32_t pad;
00039 } l4util_mb_mod_t;
00040
00041
00048 typedef struct __attribute__((packed))
00049 {
00050     l4_uint32_t struct_size;
00051     l4_uint64_t addr;
00052     l4_uint64_t size;
00053     l4_uint32_t type;
00054     /* unspecified optional padding... */
00055 } l4util_mb_addr_range_t;
00056
00058 #define MB_ARD_MEMORY 1
00059
00064 #define MB_ART_MEMORY 1
00065 #define MB_ART_RESERVED 2
00066 #define MB_ART_ACPI 3
00068 #define MB_ART_NVS 4
00069 #define MB_ART_UNUSABLE 5
00070
00071
00073 typedef struct
00074 {
00075     l4_uint32_t size;
00076     l4_uint8_t drive_number;
00077     l4_uint8_t drive_mode;
00078     l4_uint16_t drive_cylinders;
00079     l4_uint8_t drive_heads;
00080     l4_uint8_t drive_sectors;
00081     l4_uint16_t drive_ports[0];
00082 } l4util_mb_drive_t;
00083
00084 /* Drive Mode. */
00085 #define MB_DI_CHS_MODE 0
00086 #define MB_DI_LBA_MODE 1
00087
00088
00090 typedef struct
00091 {
00092     l4_uint16_t version;
00093     l4_uint16_t cseg;
00094     l4_uint32_t offset;
00095     l4_uint16_t cseg_l6;
00096     l4_uint16_t dseg_l6;
00097     l4_uint16_t flags;
00098     l4_uint16_t cseg_len;
00099     l4_uint16_t cseg_l6_len;
00100     l4_uint16_t dseg_l6_len;
00101 } __attribute__((packed)) l4util_mb_apm_t;
00102 static_assert(sizeof(l4util_mb_apm_t) == 20, "Check l4util_mb_apm_t");
00103

```

```

00104
00106 typedef struct
00107 {
00108     l4_uint8_t signature[4];
00109     l4_uint16_t version;
00110     l4_uint32_t oem_string;
00111     l4_uint32_t capabilities;
00112     l4_uint32_t video_mode;
00113     l4_uint16_t total_memory;
00114     l4_uint16_t oem_software_rev;
00115     l4_uint32_t oem_vendor_name;
00116     l4_uint32_t oem_product_name;
00117     l4_uint32_t oem_product_rev;
00118     l4_uint8_t reserved[222];
00119     l4_uint8_t oem_data[256];
00120 } __attribute__((packed)) l4util_mb_vbe_ctrl_t;
00121 static_assert(sizeof(l4util_mb_vbe_ctrl_t) == 512, "Check l4util_mb_vbe_ctrl_t");
00122
00123
00125 typedef struct
00126 {
00130     l4_uint16_t mode_attributes;
00132     l4_uint8_t win_a_attributes;
00134     l4_uint8_t win_b_attributes;
00136     l4_uint16_t win_granularity;
00138     l4_uint16_t win_size;
00140     l4_uint16_t win_a_segment;
00142     l4_uint16_t win_b_segment;
00144     l4_uint32_t win_func;
00146     l4_uint16_t bytes_per_scanline;
00148
00152     l4_uint16_t x_resolution;
00154     l4_uint16_t y_resolution;
00156     l4_uint8_t x_char_size;
00158     l4_uint8_t y_char_size;
00160     l4_uint8_t number_of_planes;
00162     l4_uint8_t bits_per_pixel;
00164     l4_uint8_t number_of_banks;
00166     l4_uint8_t memory_model;
00168     l4_uint8_t bank_size;
00170     l4_uint8_t number_of_image_pages;
00172     l4_uint8_t reserved0;
00174
00178     l4_uint8_t red_mask_size;
00180     l4_uint8_t red_field_position;
00182     l4_uint8_t green_mask_size;
00184     l4_uint8_t green_field_position;
00186     l4_uint8_t blue_mask_size;
00188     l4_uint8_t blue_field_position;
00190     l4_uint8_t reserved_mask_size;
00192     l4_uint8_t reserved_field_position;
00194     l4_uint8_t direct_color_mode_info;
00196
00200     l4_uint32_t phys_base;
00202     l4_uint32_t reserved1;
00204     l4_uint16_t reversed2;
00206
00210     l4_uint16_t linear_bytes_per_scanline;
00212     l4_uint8_t banked_number_of_image_pages;
00214     l4_uint8_t linear_number_of_image_pages;
00216     l4_uint8_t linear_red_mask_size;
00218     l4_uint8_t linear_red_field_position;
00220     l4_uint8_t linear_green_mask_size;
00222     l4_uint8_t linear_green_field_position;
00224     l4_uint8_t linear_blue_mask_size;
00226     l4_uint8_t linear_blue_field_position;
00228     l4_uint8_t linear_reserved_mask_size;
00230     l4_uint8_t linear_reserved_field_position;
00232     l4_uint32_t max_pixel_clock;
00234     l4_uint8_t reserved3[190];
00236 } __attribute__((packed)) l4util_mb_vbe_mode_t;
00237 static_assert(sizeof(l4util_mb_vbe_mode_t) == 256, "Check l4util_mb_vbe_mode_t");
00238
00239
00246
00247 typedef struct
00248 {
00249     l4_uint32_t flags;
00250     l4_uint32_t mem_lower;
00251     l4_uint32_t mem_upper;
00252     l4_uint32_t boot_device;
00253     l4_uint32_t cmdline;
00254     l4_uint32_t mods_count;
00255     l4_uint32_t mods_addr;
00256
00257     union
00258     {

```



```

00259     struct
00260     {
00262         l4_uint32_t tabsize;
00263         l4_uint32_t strsize;
00264         l4_uint32_t addr;
00265         l4_uint32_t pad;
00266     }
00267     a;
00268
00269     struct
00270     {
00272         l4_uint32_t num;
00273         l4_uint32_t size;
00274         l4_uint32_t addr;
00275         l4_uint32_t shndx;
00276     }
00277     e;
00278 }
00279 syms;
00280
00281 l4_uint32_t mmap_length;
00282 l4_uint32_t mmap_addr;
00283 l4_uint32_t drives_length;
00284 l4_uint32_t drives_addr;
00285 l4_uint32_t config_table;
00286 l4_uint32_t boot_loader_name;
00287 l4_uint32_t apm_table;
00288 l4_uint32_t vbe_ctrl_info;
00289 l4_uint32_t vbe_mode_info;
00290 l4_uint16_t vbe_mode;
00291 l4_uint16_t vbe_interface_seg;
00292 l4_uint16_t vbe_interface_off;
00293 l4_uint16_t vbe_interface_len;
00294 } l4util_mb_info_t;
00295 static_assert(sizeof(l4util_mb_info_t) == 88, "Check l4util_mb_info_t");
00296
00303 static inline l4util_mb_addr_range_t *
00304 l4util_mb_first_mmap_entry(l4util_mb_info_t *mbi)
00305 {
00306     return (l4util_mb_addr_range_t *) (l4_addr_t) mbi->mmap_addr;
00307 }
00308
00318 static inline l4util_mb_addr_range_t *
00319 l4util_mb_next_mmap_entry(l4util_mb_addr_range_t *e)
00320 {
00321     return (l4util_mb_addr_range_t *) ((l4_addr_t) e + e->struct_size
00322                                         + sizeof(e->struct_size));
00323 }
00324
00332 #define l4util_mb_for_each_mmap_entry(i, mbi)
00333     for (i = l4util_mb_first_mmap_entry(mbi);
00334          (unsigned long) i < (unsigned long) mbi->mmap_addr + mbi->mmap_length;
00335          i = l4util_mb_next_mmap_entry(i))
00336
00337 #endif /* ! __ASSEMBLY__ */
00338
00342
00344 #define L4UTIL_MB_MEMORY      0x00000001
00345
00347 #define L4UTIL_MB_BOOTDEV     0x00000002
00348
00350 #define L4UTIL_MB_CMDLINE     0x00000004
00351
00353 #define L4UTIL_MB_MODS        0x00000008
00354
00355 /* These next two are mutually exclusive */
00357 #define L4UTIL_MB_AOUT_SYMS    0x00000010
00358
00360 #define L4UTIL_MB_ELF_SHDR     0x00000020
00361
00363 #define L4UTIL_MB_MEM_MAP      0x00000040
00364
00366 #define L4UTIL_MB_DRIVE_INFO    0x00000080
00367
00369 #define L4UTIL_MB_CONFIG_TABLE 0x00000100
00370
00372 #define L4UTIL_MB_BOOT_LOADER_NAME 0x00000200
00373
00375 #define L4UTIL_MB_APM_TABLE     0x00000400
00376
00378 #define L4UTIL_MB_VIDEO_INFO    0x00000800
00379
00380
00382 #define L4UTIL_MB_VALID         0x2BADB002UL
00383 #define L4UTIL_MB_VALID_ASM     0x2BADB002
00384
00385

```

```

00386 /*****
00387  * Multiboot2
00388  *****/
00389
00390 #ifndef __ASSEMBLY__
00391
00392 typedef struct
00393 {
00394     l4_uint32_t total_size;
00395     l4_uint32_t reserved;
00396 } __attribute__((packed)) l4util_mb2_info_t;
00397
00398 typedef struct
00399 {
00400     char string[0];
00401 } __attribute__((packed)) l4util_mb2_cmdline_tag_t;
00402
00403 typedef struct
00404 {
00405     l4_uint32_t mod_start;
00406     l4_uint32_t mod_end;
00407     char string[];
00408 } __attribute__((packed)) l4util_mb2_module_tag_t;
00409
00410 typedef struct
00411 {
00412     l4_uint64_t base_addr;
00413     l4_uint64_t length;
00414     l4_uint32_t type;
00415     l4_uint32_t reserved;
00416 } __attribute__((packed)) l4util_mb2_memmap_entry_t;
00417
00418 typedef struct
00419 {
00420     l4_uint32_t entry_size;
00421     l4_uint32_t entry_version;
00422     l4util_mb2_memmap_entry_t entries[];
00423 } __attribute__((packed)) l4util_mb2_memmap_tag_t;
00424
00425 typedef struct
00426 {
00427     char data[0];
00428 } __attribute__((packed)) l4util_mb2_rsdp_tag_t;
00429
00430
00431 struct color_info_rgb_t
00432 {
00433     l4_uint8_t framebuffer_red_field_position;
00434     l4_uint8_t framebuffer_red_mask_size;
00435     l4_uint8_t framebuffer_green_field_position;
00436     l4_uint8_t framebuffer_green_mask_size;
00437     l4_uint8_t framebuffer_blue_field_position;
00438     l4_uint8_t framebuffer_blue_mask_size;
00439 } __attribute__((packed));
00440
00441 typedef struct
00442 {
00443     l4_uint64_t framebuffer_addr;
00444     l4_uint32_t framebuffer_pitch;
00445     l4_uint32_t framebuffer_width;
00446     l4_uint32_t framebuffer_height;
00447     l4_uint8_t framebuffer_bpp;
00448     l4_uint8_t framebuffer_type;
00449     l4_uint8_t reserved;
00450
00451     // color_info;
00452     union
00453     {
00454         struct color_info_rgb_t color_info_rgb;
00455     };
00456 } __attribute__((packed)) l4util_mb2_framebuffer_tag_t;
00457
00458 typedef struct
00459 {
00460     l4_uint32_t type;
00461     l4_uint32_t size;
00462
00463     union
00464     {
00465         l4util_mb2_cmdline_tag_t cmdline;
00466         l4util_mb2_module_tag_t module;
00467         l4util_mb2_memmap_tag_t memmap;
00468         l4util_mb2_framebuffer_tag_t fb;
00469         l4util_mb2_rsdp_tag_t rsdp;
00470     };
00471 } __attribute__((packed)) l4util_mb2_tag_t;
00472

```

```

00473 #endif /* ! __ASSEMBLY__ */
00474
00475
00476 #define L4UTIL_MB2_MAGIC      0xE85250D6
00477 #define L4UTIL_MB2_ARCH_I386  0x0
00478
00479 #define L4UTIL_MB2_TERMINATOR_HEADER_TAG  0
00480 #define L4UTIL_MB2_INFO_REQUEST_HEADER_TAG 1
00481 #define L4UTIL_MB2_ENTRY_ADDRESS_HEADER_TAG 3
00482 #define L4UTIL_MB2_FRAMEBUFFER_HEADER_TAG 5
00483 #define L4UTIL_MB2_RELOCATABLE_HEADER_TAG 10
00484
00485 #define L4UTIL_MB2_TAG_FLAG_REQUIRED      0
00486
00487 #define L4UTIL_MB2_TAG_ALIGN_SHIFT      3
00488 #define L4UTIL_MB2_TAG_ALIGN           8
00489
00490 #define L4UTIL_MB2_TERMINATOR_INFO_TAG      0
00491 #define L4UTIL_MB2_BOOT_CMDLINE_INFO_TAG    1
00492 #define L4UTIL_MB2_MODULE_INFO_TAG          3
00493 #define L4UTIL_MB2_MEMORY_MAP_INFO_TAG      6
00494 #define L4UTIL_MB2_FRAMEBUFFER_INFO_TAG     8
00495 #define L4UTIL_MB2_RSDP_OLD_INFO_TAG        14
00496 #define L4UTIL_MB2_RSDP_NEW_INFO_TAG        15
00497 #define L4UTIL_MB2_IMAGE_LOAD_BASE_PHYS_INFO_TAG 21
00498
00499 #define L4UTIL_MB2_RELO_PREFERRED_NONE 0
00500 #define L4UTIL_MB2_RELO_PREFERRED_MIN  1
00501 #define L4UTIL_MB2_RELO_PREFERRED_MAX  2
00502
00503 #endif

```

## 16.656 l4/util/parse\_cmd.h File Reference


comfortable command-line parsing

```

#include <stdarg.h>
#include <l4/sys/compiler.h>

```

Include dependency graph for parse\_cmd.h:



### Typedefs

- typedef void(\* **parse\_cmd\_fn\_t**) (int)  
Function type for `PARSE_CMD_FN`.
- typedef void(\* **parse\_cmd\_fn\_arg\_t**) (int, const char \*, int)  
Function type for `PARSE_CMD_FN_ARG`.

## Enumerations

- enum [parse\\_cmd\\_type](#)

*Types for parsing.*

## Functions

- [L4\\_BEGIN\\_DECLS](#) int [parse\\_cmdline](#) (int \*argc, const char \*\*\*argv, int arg0,...)

*Parse the command-line for specified arguments and store the values into variables.*

## 16.656.1 Detailed Description

comfortable command-line parsing

### Date

2002

### Author

Jork Loeser [jork.loeser@inf.tu-dresden.de](mailto:jork.loeser@inf.tu-dresden.de)

Definition in file [parse\\_cmd.h](#).

## 16.657 [parse\\_cmd.h](#)

[Go to the documentation of this file.](#)

```

00001
00008
00009 /*
00010  * (c) 2003-2009 Author(s)
00011  *     economic rights: Technische Universität Dresden (Germany)
00012  * License: see LICENSE.spdx (in this directory or the directories above)
00013  */
00014
00015 #ifndef __PARSE_CMD_H
00016 #define __PARSE_CMD_H
00017
00018 #include <stdarg.h>
00019 #include <l4/sys/compiler.h>
00020
00026
00030 enum parse_cmd_type {
00031     PARSE_CMD_INT,
00032     PARSE_CMD_SWITCH,
00033     PARSE_CMD_STRING,
00034     PARSE_CMD_FN,
00035     PARSE_CMD_FN_ARG,
00036     PARSE_CMD_INC,
00037     PARSE_CMD_DEC,
00038 };
00039
00043 typedef L4_CV void (*parse_cmd_fn_t)(int);
00044
00048 typedef L4_CV void (*parse_cmd_fn_arg_t)(int, const char*, int);
00049
00050 L4_BEGIN_DECLS
00051
00138 L4_CV int parse_cmdline(int *argc, const char***argv, int arg0, ...);
00139 L4_CV int parse_cmdlinev(int *argc, const char***argv, int arg0, va_list va);
00140 L4_CV int parse_cmdline_extra(const char*argv0, const char*line, char delim,
00141                             int arg0,...);
00142
00143 L4_END_DECLS
00145
00146 #endif
00147

```

## 16.658 printf\_helpers.h

```

00001 /*
00002  * Copyright (C) 2025 Kernkonzept GmbH.
00003  * Author(s): Frank Mehnert <frank.mehnert@kernkonzept.com>
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007
00008 #pragma once
00009
00010 #include <stddef.h>
00011 #include <stdio.h>
00012 #include <l4/sys/compiler.h>
00013
00030 L4_INLINE int l4util_human_readable_size(char *outstr, size_t outsize,
00031                                         unsigned long long bytes)
00032 {
00033     static char const *const unitstr = "BKMGT";
00034
00035     int idx = sizeof(unitstr) - 2;
00036     int order;
00037
00038     for (order = idx * 10; order > 10; order -= 10, --idx)
00039         if (bytes > (1ULL « order))
00040             break;
00041
00042     unsigned long long value = bytes » order;
00043     unsigned long long fract = (bytes - (value « order))
00044                               / ((1ULL « order) / 10 + 1);
00045
00046     return snprintf(outstr, outsize, "%llu.%11lu %ciB",
00047                    value, fract, unitstr[idx]);
00048 }

```


## 16.659 l4/util/rand.h File Reference

Simple Pseudo-Random Number Generator.

```
#include <l4/sys/compiler.h>
```

```
#include <l4/sys/l4int.h>
```

Include dependency graph for rand.h:



### Functions

- [l4\\_uint32\\_t l4util\\_rand](#) (void)

*Deliver next random number.*

- void `l4util_srand` (`l4_uint32_t` seed)

*Initialize random number generator.*

## 16.659.1 Detailed Description

Simple Pseudo-Random Number Generator.

### Date

1998

### Author

Lars Reuther `reuther@os.inf.tu-dresden.de`

Definition in file [rand.h](#).

## 16.660 rand.h

[Go to the documentation of this file.](#)

```

00001
00008 /*
00009  * (c) 2008-2009 Author(s)
00010  *      economic rights: Technische Universität Dresden (Germany)
00011  * License: see LICENSE.spdx (in this directory or the directories above)
00012  */
00013
00014 #ifndef __L4UTIL_RAND_H
00015 #define __L4UTIL_RAND_H
00016
00017 #define L4_RAND_MAX 65535
00018
00019 #include <l4/sys/compiler.h>
00020 #include <l4/sys/l4int.h>
00021
00022 L4_BEGIN_DECLS
00023
00028
00035 L4_CV l4_uint32_t
00036 l4util_rand(void);
00037
00044 L4_CV void
00045 l4util_srand (l4_uint32_t seed);
00046
00047 L4_END_DECLS
00048
00049 #endif /* __L4UTIL_RAND_H */

```

## 16.661 l4/util/splitlog2.h File Reference


Split a range in log2 aligned and size-aligned chunks.

```

#include <l4/sys/linkage.h>
#include <l4/sys/err.h>

```

#include <l4/util/bitops.h>  
 Include dependency graph for splitlog2.h:



## Functions

- `L4_BEGIN_DECLS` long `l4util_splitlog2_hdl` (`l4_addr_t` start, `l4_addr_t` end, long(\*handler)(`l4_addr_t` s, `l4_addr_t` e, int log2size))  
*Split a range into log2 base and size aligned chunks.*
- `l4_addr_t` `l4util_splitlog2_size` (`l4_addr_t` start, `l4_addr_t` end)  
*Return log2 base and size aligned length of a range.*

## 16.661.1 Detailed Description

Split a range in log2 aligned and size-aligned chunks.

Definition in file [splitlog2.h](#).

## 16.662 splitlog2.h

[Go to the documentation of this file.](#)

```

00001
00005 /*
00006  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>
00007  *     economic rights: Technische Universität Dresden (Germany)
00008  * License: see LICENSE.spdx (in this directory or the directories above)
00009  */
00010 #ifndef __L4UTIL__INCLUDE__SPLITLOG2_H__
00011 #define __L4UTIL__INCLUDE__SPLITLOG2_H__
00012
00013 #include <l4/sys/linkage.h>
00014 #include <l4/sys/err.h>
00015 #include <l4/util/bitops.h>
00016
00017 L4_BEGIN_DECLS
00018
00031 L4_INLINE long
00032 l4util_splitlog2_hdl(l4_addr_t start, l4_addr_t end,
00033                     long (*handler)(l4_addr_t s, l4_addr_t e, int log2size));
00034
00043 L4_INLINE l4_addr_t
00044 l4util_splitlog2_size(l4_addr_t start, l4_addr_t end);
00045
00046 L4_END_DECLS
00047
00048 /* Implementation */

```

```

00049
00050 L4_INLINE long
00051 l4util_splitlog2_hdl(l4_addr_t start, l4_addr_t end,
00052                     long (*handler)(l4_addr_t s, l4_addr_t e, int log2size))
00053 {
00054     if (end < start)
00055         return -L4_EINVAL;
00056
00057     while (start <= end)
00058     {
00059         long retval;
00060         int len2 = l4util_splitlog2_size(start, end);
00061         l4_addr_t len = 1UL << len2;
00062         if ((retval = handler(start, start + len - 1, len2)))
00063             return retval;
00064         start += len;
00065     }
00066     return 0;
00067 }
00068
00069 L4_INLINE l4_addr_t
00070 l4util_splitlog2_size(l4_addr_t start, l4_addr_t end)
00071 {
00072     int start_bits = l4util_bsf(start);
00073     int len_bits = l4util_bsr(end - start + 1);
00074     if (start_bits != -1 && len_bits > start_bits)
00075         len_bits = start_bits;
00076
00077     return len_bits;
00078 }
00079
00080 #endif /* ! __L4UTIL__INCLUDE__SPLITLOG2_H__ */

```

## 16.663 util.h

```

00001
00004 /*
00005  * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00006  *      Alexander Warg <warg@os.inf.tu-dresden.de>,
00007  *      Frank Mehnert <fm3@os.inf.tu-dresden.de>
00008  *      economic rights: Technische Universität Dresden (Germany)
00009  * License: see LICENSE.spdx (in this directory or the directories above)
00010  */
00011 #ifndef __L4UTIL__UTIL_H__
00012 #define __L4UTIL__UTIL_H__
00013
00014 #include <l4/sys/types.h>
00015 #include <l4/sys/compiler.h>
00016 #include <l4/sys/ipc.h>
00017
00021
00022 L4_BEGIN_DECLS
00023
00034 L4_CV l4_timeout_s l4util_micros2l4to(l4_uint64_t us) L4_NOTHROW;
00035
00041 L4_CV void l4_sleep(l4_uint32_t ms) L4_NOTHROW;
00042
00049 L4_CV void l4_usleep(l4_uint64_t us) L4_NOTHROW;
00050
00056 L4_INLINE void l4_sleep_forever(void) L4_NOTHROW L4_NORETURN;
00057
00065 L4_INLINE void
00066 l4_touch_ro(const void *addr, unsigned size) L4_NOTHROW;
00067
00075 L4_INLINE void
00076 l4_touch_rw(const void *addr, unsigned size) L4_NOTHROW;
00077
00078
00079
00080 /*
00081  * Implementations
00082  */
00083
00084 L4_INLINE void
00085 l4_sleep_forever(void) L4_NOTHROW
00086 {
00087     for (;;)
00088         l4_ipc_sleep(L4_IPC_NEVER);
00089 }
00090
00091 L4_INLINE void
00092 l4_touch_ro(const void *addr, unsigned size) L4_NOTHROW
00093 {

```



```

00094     l4_addr_t b, e;
00095
00096     b = l4_trunc_page((l4_addr_t)addr);
00097     e = l4_trunc_page((l4_addr_t)addr + size - 1);
00098
00099     for (; b <= e; b += L4_PAGESIZE)
00100         (void) (*(volatile char *)b);
00101 }
00102
00103
00104 L4_INLINE void
00105 l4_touch_rw(const void *addr, unsigned size) L4_NOTHROW
00106 {
00107     l4_addr_t b, e;
00108
00109     b = l4_trunc_page((l4_addr_t)addr);
00110     e = l4_trunc_page((l4_addr_t)addr + size - 1);
00111
00112     for (; b <= e; b += L4_PAGESIZE)
00113         *(volatile char *)b |= 0;
00114 }
00115
00116 L4_END_DECLS
00117
00118 #endif /* __L4UTIL__UTIL_H__ */

```

## 16.664 vbus

```

00001 // vi:set ft=cpp: -*- Mode: C++ -*-
00002 /*
00003  * (c) 2011 Adam Lackorzynski <adam@os.inf.tu-dresden.de>
00004  *     economic rights: Technische Universität Dresden (Germany)
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00008 #pragma once
00009
00010 #include <l4/vbus/vbus.h>
00011 #include <l4/vbus/vbus_pm.h>
00012 #include <l4/sys/icu>
00013
00014 #include <l4/re/dataspace>
00015 #include <l4/re/dma_space>
00016 #include <l4/re/event>
00017 #include <l4/re/inhibitor>
00018
00036
00040 namespace L4vbus {
00041
00042     class Vbus;
00043
00049     template<typename DEC>
00050     class Pm
00051     {
00052     private:
00053         DEC const *self() const { return static_cast<DEC const *>(this); }
00054         DEC *self() { return static_cast<DEC *>(this); }
00055     public:
00063         int pm_suspend() const
00064         { return l4vbus_pm_suspend(self()->bus_cap().cap(), self()->dev_handle()); }
00065
00074         int pm_resume() const
00075         { return l4vbus_pm_resume(self()->bus_cap().cap(), self()->dev_handle()); }
00076     };
00077
00078
00083     class Device : public Pm<Device>
00084     {
00085     public:
00089         Device() : _dev(L4VBUS_NULL) {}
00090
00100         Device(L4::Cap<Vbus> bus, l4vbus_device_handle_t dev)
00101         : _bus(bus), _dev(dev) {}
00102
00107         L4::Cap<Vbus> bus_cap() const { return _bus; }
00108
00116         l4vbus_device_handle_t dev_handle() const { return _dev; }
00117
00118
00148         int device_by_hid(Device *child, char const *hid,
00149                             int depth = L4VBUS_MAX_DEPTH,
00150                             l4vbus_device_t *devinfo = 0) const
00151         {

```

```

00152     child->_bus = _bus;
00153     return l4vbus_get_device_by_hid(_bus.cap(), _dev, &child->_dev, hid,
00154                                     depth, devinfo);
00155 }
00156
00171 int next_device(Device *child, int depth = L4VBUS_MAX_DEPTH,
00172                l4vbus_device_t *devinfo = 0) const
00173 {
00174     child->_bus = _bus;
00175     return l4vbus_get_next_device(_bus.cap(), _dev, &child->_dev, depth,
00176                                   devinfo);
00177 }
00178
00189 int device(l4vbus_device_t *devinfo) const
00190 { return l4vbus_get_device(_bus.cap(), _dev, devinfo); }
00191
00209 int get_resource(unsigned res_idx, l4vbus_resource_t *res) const
00210 {
00211     return l4vbus_get_resource(_bus.cap(), _dev, res_idx, res);
00212 }
00213
00223 int is_compatible(char const *cid) const
00224 { return l4vbus_is_compatible(_bus.cap(), _dev, cid); }
00225
00230 bool operator == (Device const &o) const
00231 {
00232     return _bus == o._bus && _dev == o._dev;
00233 }
00234
00239 bool operator != (Device const &o) const
00240 {
00241     return _bus != o._bus || _dev != o._dev;
00242 }
00243
00244 protected:
00245     L4::Cap<Vbus> _bus;
00247     l4vbus_device_handle_t _dev;
00248 };
00249
00260 class Icu : public Device
00261 {
00262 public:
00264     enum Src_types
00265     {
00273         Src_dev_handle = L4VBUS_ICU_SRC_DEV_HANDLE
00274     };
00275
00285     int vicu(L4::Cap<L4::Icu> icu) const
00286     {
00287         return l4vbus_vicu_get_cap(_bus.cap(), _dev, icu.cap());
00288     }
00289 };
00290
00298 class Vbus : public L4::Kobject_3t<Vbus, L4Re::Dataspace, L4Re::Inhibitor, L4Re::Event>
00299 {
00300 public:
00301
00311     int request_ioport(l4vbus_resource_t *res) const
00312     {
00313         return l4vbus_request_ioport(cap(), res);
00314     }
00315
00323     int release_ioport(l4vbus_resource_t *res) const
00324     {
00325         return l4vbus_release_ioport(cap(), res);
00326     }
00327
00336     Device root() const
00337     {
00338         return Device(L4::Cap<Vbus>(cap()), L4VBUS_ROOT_BUS);
00339     }
00340
00357     int assign_dma_domain(unsigned domain_id, unsigned flags,
00358                           L4::Cap<L4Re::Dma_space> dma_space) const
00359     {
00360         flags |= L4VBUS_DMAD_L4RE_DMA_SPACE;
00361         flags &= ~L4VBUS_DMAD_KERNEL_DMA_SPACE;
00362         return l4vbus_assign_dma_domain(cap(), domain_id, flags, dma_space.cap());
00363     }
00364
00382     int assign_dma_domain(unsigned domain_id, unsigned flags,
00383                           L4::Cap<L4::Task> dma_space) const
00384     {
00385         flags |= L4VBUS_DMAD_KERNEL_DMA_SPACE;
00386         flags &= ~L4VBUS_DMAD_L4RE_DMA_SPACE;
00387         return l4vbus_assign_dma_domain(cap(), domain_id, flags, dma_space.cap());
00388     }

```

```

00389
00390     typedef L4::Typeid::Raw_ipc<Vbus> Rpc;
00391 };
00392
00393 } // namespace L4vbus

```

## 16.665 I4/vbus/vbus.h File Reference


Description of the vbus C API.

```


#include <l4/sys/compiler.h>
#include <l4/vbus/vbus_types.h>
#include <l4/sys/types.h>

```

Include dependency graph for vbus.h:



This graph shows which files directly or indirectly include this file:



## Enumerations

- enum { `L4VBUS_NULL` = -1L , `L4VBUS_ROOT_BUS` = 0 }  
*Constants for device nodes.*
- enum `l4vbus_icu_src_types` { `L4VBUS_ICU_SRC_DEV_HANDLE` = 1ULL << 63 }  
*Flags that can be used with the ICU on a vbus device.*
- enum `L4vbus_dma_domain_assign_flags` { `L4VBUS_DMAD_UNBIND` = 0 , `L4VBUS_DMAD_BIND` = 1 , `L4VBUS_DMAD_L4RE_DMA_SPACE` = 0 , `L4VBUS_DMAD_KERNEL_DMA_SPACE` = 2 }  
*Flags for `l4vbus_assign_dma_domain()`.*

## Functions

- `L4_BEGIN_DECLS` int `l4vbus_get_device_by_hid` (`l4_cap_idx_t` vbus, `l4vbus_device_handle_t` parent, `l4vbus_device_handle_t` \*child, char const \*hid, int depth, `l4vbus_device_t` \*devinfo)  
*Find a device by the hardware interface identifier (HID).*
- int `l4vbus_get_next_device` (`l4_cap_idx_t` vbus, `l4vbus_device_handle_t` parent, `l4vbus_device_handle_t` \*child, int depth, `l4vbus_device_t` \*devinfo)  
*Find next child following `child`.*
- int `l4vbus_get_device` (`l4_cap_idx_t` vbus, `l4vbus_device_handle_t` dev, `l4vbus_device_t` \*devinfo)  
*Obtain detailed information about a Vbus device.*
- int `l4vbus_get_resource` (`l4_cap_idx_t` vbus, `l4vbus_device_handle_t` dev, unsigned res\_idx, `l4vbus_resource_t` \*res)  
*Obtain the resource description of an individual device resource.*
- int `l4vbus_is_compatible` (`l4_cap_idx_t` vbus, `l4vbus_device_handle_t` dev, char const \*cid)  
*Check if the given device has a compatibility ID (CID) or HID that matches `cid`.*
- int `l4vbus_get_hid` (`l4_cap_idx_t` vbus, `l4vbus_device_handle_t` dev, char \*hid, unsigned long max\_len)  
*Get the HID (hardware identifier) of a device.*
- int `l4vbus_get_adr` (`l4_cap_idx_t` vbus, `l4vbus_device_handle_t` dev, `l4_uint32_t` \*adr)  
*Get the bus-specific address of a device.*
- int `l4vbus_request_ioport` (`l4_cap_idx_t` vbus, `l4vbus_resource_t` const \*res)  
*Request an IO port resource.*
- int `l4vbus_assign_dma_domain` (`l4_cap_idx_t` vbus, unsigned domain\_id, unsigned flags, `l4_cap_idx_t` dma\_space)  
*Bind or unbind a kernel *DMA space* or a *L4Re::Dma space* to a DMA domain.*
- int `l4vbus_release_ioport` (`l4_cap_idx_t` vbus, `l4vbus_resource_t` const \*res)  
*Release a previously requested IO port resource.*
- int `l4vbus_vicu_get_cap` (`l4_cap_idx_t` vbus, `l4vbus_device_handle_t` icu, `l4_cap_idx_t` cap)  
*Get capability of ICU.*

## 16.665.1 Detailed Description

Description of the vbus C API.

Definition in file [vbus.h](#).

## 16.665.2 Enumeration Type Documentation

### 16.665.2.1 anonymous enum

anonymous enum

Constants for device nodes.

#### Enumerator

L4VBUS_NULL	NULL device.
L4VBUS_ROOT_BUS	Root device on the vbus.

Definition at line 20 of file [vbus.h](#).

### 16.665.2.2 l4vbus\_icu\_src\_types

enum [l4vbus\\_icu\\_src\\_types](#)

Flags that can be used with the ICU on a vbus device.

#### Enumerator

L4VBUS_ICU_SRC_DEV_HANDLE	Flag to denote that the value should be interpreted as a device handle. This flag may be used in the <code>source</code> parameter in <a href="#">l4_icu_msi_info()</a> to denote that the ICU should interpret the source ID as a device handle.
---------------------------	---

Definition at line 26 of file [vbus.h](#).

## 16.666 vbus.h

[Go to the documentation of this file.](#)

```
00001 /*
00002  * (c) 2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00003  *      Alexander Warg <warg@os.inf.tu-dresden.de>,
00004  *      Torsten Frenzel <frenzel@os.inf.tu-dresden.de>
00005  *      economic rights: Technische Universität Dresden (Germany)
00006  *
00007  * License: see LICENSE.spdx (in this directory or the directories above)
00008  */
00013 #pragma once
00014
00015 #include <l4/sys/compiler.h>
00016 #include <l4/vbus/vbus_types.h>
00017 #include <l4/sys/types.h>
00018
00020 enum {
00021     L4VBUS_NULL = -1L,
00022     L4VBUS_ROOT_BUS = 0,
00023 };
00024
00026 enum l4vbus_icu_src_types {
00033     L4VBUS_ICU_SRC_DEV_HANDLE = 1ULL << 63
00034 };
00035
00053
00054 L4_BEGIN_DECLS
00055
```

```

00063 int L4_CV
00064 l4vbus_get_device_by_hid(l4_cap_idx_t vbus, l4vbus_device_handle_t parent,
00065                          l4vbus_device_handle_t *child, char const *hid,
00066                          int depth, l4vbus_device_t *devinfo);
00067
00083 int L4_CV
00084 l4vbus_get_next_device(l4_cap_idx_t vbus, l4vbus_device_handle_t parent,
00085                       l4vbus_device_handle_t *child, int depth,
00086                       l4vbus_device_t *devinfo);
00087
00101 int L4_CV
00102 l4vbus_get_device(l4_cap_idx_t vbus, l4vbus_device_handle_t dev,
00103                  l4vbus_device_t *devinfo);
00104
00113 int L4_CV
00114 l4vbus_get_resource(l4_cap_idx_t vbus, l4vbus_device_handle_t dev,
00115                    unsigned res_idx, l4vbus_resource_t *res);
00116
00117
00124 int L4_CV
00125 l4vbus_is_compatible(l4_cap_idx_t vbus, l4vbus_device_handle_t dev,
00126                     char const *cid);
00127
00138 int L4_CV
00139 l4vbus_get_hid(l4_cap_idx_t vbus, l4vbus_device_handle_t dev, char *hid,
00140               unsigned long max_len);
00141
00152 int L4_CV
00153 l4vbus_get_adr(l4_cap_idx_t vbus, l4vbus_device_handle_t dev, l4_uint32_t *adr);
00154
00168 int L4_CV
00169 l4vbus_request_ioport(l4_cap_idx_t vbus, l4vbus_resource_t const *res);
00170
00174 enum L4vbus_dma_domain_assign_flags
00175 {
00177     L4VBUS_DMAD_UNBIND = 0,
00179     L4VBUS_DMAD_BIND   = 1,
00181     L4VBUS_DMAD_L4RE_DMA_SPACE = 0,
00183     L4VBUS_DMAD_KERNEL_DMA_SPACE = 2,
00184 };
00185
00207 int L4_CV
00208 l4vbus_assign_dma_domain(l4_cap_idx_t vbus, unsigned domain_id,
00209                        unsigned flags, l4_cap_idx_t dma_space);
00210
00219 int L4_CV
00220 l4vbus_release_ioport(l4_cap_idx_t vbus, l4vbus_resource_t const *res);
00221
00231 int L4_CV
00232 l4vbus_vicu_get_cap(l4_cap_idx_t vbus, l4vbus_device_handle_t icu,
00233                   l4_cap_idx_t cap);
00234
00235 L4_END_DECLS
00236

```

## 16.667 vbus\_generic

```

00001 // vi:set ft=c++: -*- Mode: C++ -*-
00002 /*
00003  * (c) 2009 Alexander Warg <warg@os.inf.tu-dresden.de>,
00004  *      Torsten Frenzel <frenzel@os.inf.tu-dresden.de>
00005  *      economic rights: Technische Universität Dresden (Germany)
00006  *
00007  * License: see LICENSE.spdx (in this directory or the directories above)
00008  */
00009
00010 #pragma once
00011
00012 #include <l4/cxx/ipc_stream>
00013 #include <l4/vbus/vbus_types.h>
00014 #include <l4/vbus/vbus>
00015
00016 inline void
00017 l4vbus_device_msg(l4vbus_device_handle_t handle, l4_uint32_t op,
00018                  L4::Ipc::Iostream &s)
00019 {
00020     s << handle << op;
00021 }

```

## 16.668 vbus\_gpio

```

00001 // vi:set ft=c++: -*- Mode: C++ -*-
00002 /*
00003  * (c) 2011 Adam Lackorzynski <adam@os.inf.tu-dresden.de>
00004  *      economic rights: Technische Universität Dresden (Germany)
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00008 #pragma once
00009
00010 #include <l4/vbus/vbus>
00011 #include <l4/vbus/vbus_gpio.h>
00012
00013 namespace L4vbus {
00014
00015     class Gpio_pin : public Device
00016     {
00017     public:
00018         Gpio_pin(Device const &dev, unsigned pin)
00019             : Device(dev), _pin(pin)
00020         {}
00021
00022         int get() const
00023         {
00024             return l4vbus_gpio_get(_bus.cap(), _dev, _pin);
00025         }
00026
00027         int set(int value) const
00028         {
00029             return l4vbus_gpio_set(_bus.cap(), _dev, _pin, value);
00030         }
00031
00032         int setup(unsigned mode, unsigned value) const
00033         {
00034             return l4vbus_gpio_setup(_bus.cap(), _dev, _pin, mode, value);
00035         }
00036
00037         int config_pull(unsigned mode) const
00038         {
00039             return l4vbus_gpio_config_pull(_bus.cap(), _dev, _pin, mode);
00040         }
00041
00042         int config_pad(unsigned func, unsigned value) const
00043         {
00044             return l4vbus_gpio_config_pad(_bus.cap(), _dev, _pin, func, value);
00045         }
00046
00047         int config_get(unsigned func, unsigned *value) const
00048         {
00049             return l4vbus_gpio_config_get(_bus.cap(), _dev, _pin, func, value);
00050         }
00051
00052         int to_irq() const
00053         {
00054             return l4vbus_gpio_to_irq(_bus.cap(), _dev, _pin);
00055         }
00056
00057         unsigned pin() const { return _pin; }
00058
00059     protected:
00060         Gpio_pin() {}
00061         unsigned _pin;
00062     };
00063
00064     class Gpio_module : public Device
00065     {
00066     public:
00067         Gpio_module(Device dev)
00068             : Device(dev)
00069         {}
00070
00071         struct Pin_slice
00072         {
00073             Pin_slice(unsigned offset, unsigned mask) : offset(offset), mask(mask) {}
00074             unsigned offset, mask;
00075         };
00076
00077         int setup(Pin_slice const &mask, unsigned mode, unsigned value) const
00078         {
00079             return l4vbus_gpio_multi_setup(_bus.cap(), _dev, mask.offset, mask.mask,
00080                                             mode, value);
00081         }
00082
00083         int config_pad(Pin_slice const &mask, unsigned func, unsigned value) const

```

```

00186 {
00187     return l4vbus_gpio_multi_config_pad(_bus.cap(), _dev, mask.offset,
00188                                         mask.mask, func, value);
00189 }
00190
00201 int get(unsigned offset, unsigned *data) const
00202 {
00203     return l4vbus_gpio_multi_get(_bus.cap(), _dev, offset, data);
00204 }
00205
00217 int set(Pin_slice const &mask, unsigned data)
00218 {
00219     return l4vbus_gpio_multi_set(_bus.cap(), _dev, mask.offset,
00220                                   mask.mask, data);
00221 }
00222
00229 Gpio_pin pin(unsigned pin) const
00230 {
00231     return Gpio_pin(*this, pin);
00232 }
00233
00234 protected:
00235     Gpio_module() {}
00236 };
00237
00238 }

```

## 16.669 vbus\_gpio-ops.h

```

00001 /*
00002  * (c) 2011 Alexander Warg <warg@os.inf.tu-dresden.de>
00003  *     economic rights: Technische Universität Dresden (Germany)
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007
00008 #pragma once
00009
00010 #include <l4/vbus/vbus_interfaces.h>
00011
00012 enum L4vbus_gpio_op
00013 {
00014     L4VBUS_GPIO_OP_SETUP = L4VBUS_INTERFACE_GPIO << L4VBUS_IFACE_SHIFT,
00015     L4VBUS_GPIO_OP_CONFIG_PAD,
00016     L4VBUS_GPIO_OP_CONFIG_GET,
00017     L4VBUS_GPIO_OP_GET,
00018     L4VBUS_GPIO_OP_SET,
00019     L4VBUS_GPIO_OP_MULTI_SETUP,
00020     L4VBUS_GPIO_OP_MULTI_CONFIG_PAD,
00021     L4VBUS_GPIO_OP_MULTI_GET,
00022     L4VBUS_GPIO_OP_MULTI_SET,
00023     L4VBUS_GPIO_OP_TO_IRQ,
00024     L4VBUS_GPIO_OP_CONFIG_PULL
00025 };

```

## 16.670 vbus\_gpio.h

```

00001 /*
00002  * (c) 2011 Alexander Warg <warg@os.inf.tu-dresden.de>
00003  *     economic rights: Technische Universität Dresden (Germany)
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007 #pragma once
00008
00009 #include <l4/sys/compiler.h>
00010 #include <l4/sys/types.h>
00011 #include <l4/vbus/vbus_types.h>
00012
00013
00014 L4_BEGIN_DECLS
00015
00024 enum L4vbus_gpio_generic_func
00025 {
00026     L4VBUS_GPIO_SETUP_INPUT = 0x100,
00027     L4VBUS_GPIO_SETUP_OUTPUT = 0x200,
00028     L4VBUS_GPIO_SETUP_IRQ = 0x300,
00029 };

```



```

00030
00034 enum L4vbus_gpio_pull_modes
00035 {
00036     L4VBUS_GPIO_PIN_PULL_NONE = 0x100,
00037     L4VBUS_GPIO_PIN_PULL_UP   = 0x200,
00038     L4VBUS_GPIO_PIN_PULL_DOWN = 0x300,
00039 };
00040
00048 int L4_CV
00049 l4vbus_gpio_setup(l4_cap_idx_t vbus, l4vbus_device_handle_t handle,
00050                  unsigned pin, unsigned mode, int value);
00051
00059 int L4_CV
00060 l4vbus_gpio_config_pull(l4_cap_idx_t vbus, l4vbus_device_handle_t handle,
00061                       unsigned pin, unsigned mode);
00062
00070 int L4_CV
00071 l4vbus_gpio_config_pad(l4_cap_idx_t vbus, l4vbus_device_handle_t handle,
00072                      unsigned pin, unsigned func, unsigned value);
00073
00081 int L4_CV
00082 l4vbus_gpio_config_get(l4_cap_idx_t vbus, l4vbus_device_handle_t handle,
00083                      unsigned pin, unsigned func, unsigned *value);
00084
00092 int L4_CV
00093 l4vbus_gpio_get(l4_cap_idx_t vbus, l4vbus_device_handle_t handle,
00094               unsigned pin);
00095
00103 int L4_CV
00104 l4vbus_gpio_set(l4_cap_idx_t vbus, l4vbus_device_handle_t handle,
00105               unsigned pin, int value);
00106
00115 int L4_CV
00116 l4vbus_gpio_multi_setup(l4_cap_idx_t vbus, l4vbus_device_handle_t handle,
00117                       unsigned offset, unsigned mask,
00118                       unsigned mode, unsigned value);
00119
00128 int L4_CV
00129 l4vbus_gpio_multi_config_pad(l4_cap_idx_t vbus, l4vbus_device_handle_t handle,
00130                            unsigned offset, unsigned mask,
00131                            unsigned func, unsigned value);
00132
00139 int L4_CV
00140 l4vbus_gpio_multi_get(l4_cap_idx_t vbus, l4vbus_device_handle_t handle,
00141                    unsigned offset, unsigned *data);
00142
00151 int L4_CV
00152 l4vbus_gpio_multi_set(l4_cap_idx_t vbus, l4vbus_device_handle_t handle,
00153                    unsigned offset, unsigned mask, unsigned data);
00154
00162 int L4_CV
00163 l4vbus_gpio_to_irq(l4_cap_idx_t vbus, l4vbus_device_handle_t handle,
00164                  unsigned pin);
00165
00167
00168 L4_END_DECLS

```

## 16.671 vbus\_i2c.h

```

00001 /*
00002  * (c) 2009 Torsten Frenzel <frenzel@os.inf.tu-dresden.de>
00003  *     economic rights: Technische Universität Dresden (Germany)
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007 #pragma once
00008
00009 #include <l4/sys/compiler.h>
00010 #include <l4/sys/types.h>
00011 #include <l4/vbus/vbus_types.h>
00012
00013 L4_BEGIN_DECLS
00014
00015 int L4_CV
00016 l4vbus_i2c_write(l4_cap_idx_t vbus, l4vbus_device_handle_t handle,
00017                l4_uint16_t addr, l4_uint8_t sub_addr,
00018                l4_uint8_t *buffer, unsigned long size);
00019
00020 int L4_CV
00021 l4vbus_i2c_read(l4_cap_idx_t vbus, l4vbus_device_handle_t handle,
00022               l4_uint16_t addr, l4_uint8_t sub_addr,
00023               l4_uint8_t *buffer, unsigned long *size);
00024
00025 L4_END_DECLS

```

## 16.672 vbus\_inhibitor.h

```

00001
00006 #pragma once
00007
00008 enum Vbus_inhibitor
00009 {
00010     L4VBUS_INHIBITOR_SUSPEND = 0,
00011     L4VBUS_INHIBITOR_SHUTDOWN = 1,
00012     L4VBUS_INHIBITOR_REBOOT = L4VBUS_INHIBITOR_SHUTDOWN,
00013     L4VBUS_INHIBITOR_WAKEUP = 2,
00014     L4VBUS_INHIBITOR_MAX
00015 };
00016


```

## 16.673 l4/vbus/vbus\_interfaces.h File Reference


This header contains the definition of VBUS sub-interfaces and convenience functions to work with the interface IDs.

```
#include <l4/sys/types.h>
```

Include dependency graph for vbus\_interfaces.h:



This graph shows which files directly or indirectly include this file:



### Typedefs

- typedef enum `l4vbus_iface_type_t` `l4vbus_iface_type_t`  
Different sub-interfaces a vbus device may support.

## Enumerations

- enum [l4vbus\\_iface\\_type\\_t](#) {  
[L4VBUS\\_INTERFACE\\_ICU](#) = 0 , [L4VBUS\\_INTERFACE\\_GPIO](#) , [L4VBUS\\_INTERFACE\\_PCI](#) , [L4VBUS\\_INTERFACE\\_PCIDEV](#) ,  
[L4VBUS\\_INTERFACE\\_PM](#) , [L4VBUS\\_INTERFACE\\_BUS](#) , [L4VBUS\\_INTERFACE\\_GENERIC](#) = 0x20 }  
*Different sub-interfaces a vbus device may support.*
- enum { [L4VBUS\\_IFACE\\_SHIFT](#) = 26 }

## Functions

- unsigned [l4vbus\\_subinterface](#) (unsigned opcode)  
*Return the ID of the vbus sub-interface.*
- unsigned [l4vbus\\_interface\\_opcode](#) (unsigned opcode)  
*Return the function opcode within the sub-interface of the vbus command.*
- int [l4vbus\\_subinterface\\_supported](#) ([l4\\_uint32\\_t](#) dev\_type, [l4vbus\\_iface\\_type\\_t](#) iface\_type)  
*Check if a vbus device supports a given sub-interface.*

## 16.673.1 Detailed Description

This header contains the definition of VBUS sub-interfaces and convenience functions to work with the interface IDs.

Definition in file [vbus\\_interfaces.h](#).

## 16.673.2 Typedef Documentation

### 16.673.2.1 l4vbus\_iface\_type\_t

```
typedef enum l4vbus_iface_type_t l4vbus_iface_type_t
```

Different sub-interfaces a vbus device may support.

The IPC interface of vbus devices is divided into functional groups of sub-interfaces. Every device must implement the generic interface which provides general device information. According to the type of device, additional functionality may be supported.

The sub-interface constants are first of all used to divide the function opcode space of the interface into these functional groups (see [L4VBUS\\_IFACE\\_SHIFT](#)). They also make up a bitmask that specify the type of the device, i.e. from the point of view of the client a device is defined by the kinds of sub-interfaces it supports.

## 16.673.3 Enumeration Type Documentation

### 16.673.3.1 anonymous enum

anonymous enum

#### Enumerator

L4VBUS_IFACE_SHIFT	Sub-interface ID shift. Divides the function opcode sent via IPC into a sub-interface ID and the actual function opcode within the sub-interface.
--------------------	---

Definition at line 48 of file [vbus\\_interfaces.h](#).

### 16.673.3.2 l4vbus\_iface\_type\_t

enum [l4vbus\\_iface\\_type\\_t](#)

Different sub-interfaces a vbus device may support.

The IPC interface of vbus devices is divided into functional groups of sub-interfaces. Every device must implement the generic interface which provides general device information. According to the type of device, additional functionality may be supported.

The sub-interface constants are first of all used to divide the function opcode space of the interface into these functional groups (see L4VBUS\_IFACE\_SHIFT). They also make up a bitmask that specify the type of the device, i.e. from the point of view of the client a device is defined by the kinds of sub-interfaces it supports.

#### Enumerator

L4VBUS_INTERFACE_ICU	Interrupt Controller.
L4VBUS_INTERFACE_GPIO	GPIO.
L4VBUS_INTERFACE_PCI	PCI.
L4VBUS_INTERFACE_PCIDEV	PCI Device.
L4VBUS_INTERFACE_PM	Power Management.
L4VBUS_INTERFACE_BUS	VBus.
L4VBUS_INTERFACE_GENERIC	No specific sub interface.

Definition at line 29 of file [vbus\\_interfaces.h](#).

## 16.673.4 Function Documentation

### 16.673.4.1 l4vbus\_subinterface\_supported()

```
int l4vbus_subinterface_supported (
    l4_uint32_t dev_type,
    l4vbus_iface_type_t iface_type) [inline]
```

Check if a vbus device supports a given sub-interface.

**Parameters**

<i>dev_type</i>	Device type as reported in <a href="#">l4vbus_device_t</a> .
<i>iface_type</i>	Sub-interface type to check for.

**Returns**

True if the device supports the sub-interface.

Definition at line 99 of file [vbus\\_interfaces.h](#).

References [L4\\_INLINE](#), and [L4VBUS\\_INTERFACE\\_GENERIC](#).

**16.674 vbus\_interfaces.h**

[Go to the documentation of this file.](#)

```

00001 /*
00002  * (c) 2014 Sarah Hoffmann <sarah.hoffmann@kernkonzept.com>
00003  *
00004  * License: see LICENSE.spdx (in this directory or the directories above)
00005  */
00011 #pragma once
00012
00013 #include <l4/sys/types.h>
00014
00029 typedef enum l4vbus_iface_type_t
00030 {
00032     L4VBUS_INTERFACE_ICU = 0,
00034     L4VBUS_INTERFACE_GPIO,
00036     L4VBUS_INTERFACE_PCI,
00038     L4VBUS_INTERFACE_PCIDEV,
00040     L4VBUS_INTERFACE_PM,
00042     L4VBUS_INTERFACE_BUS,
00044     L4VBUS_INTERFACE_GENERIC = 0x20
00045 } l4vbus_iface_type_t;
00046
00047
00048 enum {
00056     L4VBUS_IFACE_SHIFT = 26
00057 };
00058
00070 L4_INLINE unsigned l4vbus_subinterface(unsigned opcode)
00071 {
00072     return opcode » L4VBUS_IFACE_SHIFT;
00073 }
00074
00086 L4_INLINE unsigned l4vbus_interface_opcode(unsigned opcode)
00087 {
00088     return opcode & ((1 « L4VBUS_IFACE_SHIFT) - 1);
00089 }
00090
00099 L4_INLINE int l4vbus_subinterface_supported(l4_uint32_t dev_type,
00100                                              l4vbus_iface_type_t iface_type)
00101 {
00102     if (iface_type == L4VBUS_INTERFACE_GENERIC)
00103         return 1;
00104
00105     return (dev_type & (1 « iface_type)) ? 1 : 0;
00106 }

```

**16.675 vbus\_mcspi.h**

```

00001 /*
00002  * (c) 2009 Torsten Frenzel <frenzel@os.inf.tu-dresden.de>
00003  *     economic rights: Technische Universität Dresden (Germany)
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)

```

```

00006  */
00007  #pragma once
00008
00009  #include <l4/sys/compiler.h>
00010  #include <l4/sys/types.h>
00011  #include <l4/vbus/vbus_types.h>
00012
00013  L4_BEGIN_DECLS
00014
00015  int L4_CV
00016  l4vbus_mcspi_read(l4_cap_idx_t vbus, l4vbus_device_handle_t handle,
00017                  unsigned channel, l4_umword_t *value);
00018
00019  int L4_CV
00020  l4vbus_mcspi_write(l4_cap_idx_t vbus, l4vbus_device_handle_t handle,
00021                   unsigned channel, l4_umword_t value);
00022
00023  L4_END_DECLS

```

## 16.676 vbus\_pci

```

00001  // vi:set ft=cpp: -*- Mode: C++ -*-
00002  /*
00003   * (c) 2014 Sarah Hoffmann <sarah.hoffmann@kernkonzept.com>
00004   *
00005   * License: see LICENSE.spdx (in this directory or the directories above)
00006   */
00007
00008  #pragma once
00009
00010  #include <l4/vbus/vbus>
00011  #include <l4/vbus/vbus_pci.h>
00012
00013
00014
00015  namespace L4vbus {
00016
00017
00018
00019  class Pci_host_bridge : public Device
00020  {
00021  public:
00022    int cfg_read(l4_uint32_t bus, l4_uint32_t devfn, l4_uint32_t reg,
00023                l4_uint32_t *value, l4_uint32_t width) const
00024    {
00025      return l4vbus_pci_cfg_read(bus_cap().cap(), _dev, bus,
00026                                devfn, reg, value, width);
00027    }
00028
00029    int cfg_write(l4_uint32_t bus, l4_uint32_t devfn, l4_uint32_t reg,
00030                 l4_uint32_t value, l4_uint32_t width) const
00031    {
00032      return l4vbus_pci_cfg_write(bus_cap().cap(), _dev, bus,
00033                                  devfn, reg, value, width);
00034    }
00035
00036    int irq_enable(l4_uint32_t bus, l4_uint32_t devfn, int pin,
00037                  unsigned char *trigger, unsigned char *polarity) const
00038    {
00039      return l4vbus_pci_irq_enable(bus_cap().cap(), _dev, bus,
00040                                   devfn, pin, trigger, polarity);
00041    }
00042  };
00043
00044  class Pci_dev : public Device
00045  {
00046  public:
00047    int cfg_read(l4_uint32_t reg, l4_uint32_t *value,
00048                l4_uint32_t width) const
00049    {
00050      return l4vbus_pcidev_cfg_read(bus_cap().cap(), _dev, reg, value, width);
00051    }
00052
00053    int cfg_write(l4_uint32_t reg, l4_uint32_t value,
00054                  l4_uint32_t width) const
00055    {
00056      return l4vbus_pcidev_cfg_write(bus_cap().cap(), _dev, reg, value, width);
00057    }
00058
00059    int irq_enable(unsigned char *trigger, unsigned char *polarity) const
00060    {
00061      return l4vbus_pci_irq_enable(bus_cap().cap(), _dev, bus,
00062                                   devfn, pin, trigger, polarity);
00063    }
00064  };
00065
00066
00067
00068
00069
00070
00071
00072
00073
00074
00075
00076
00077
00078
00079
00080
00081
00082
00083
00084
00085
00086
00087
00088
00089
00090
00091
00092
00093
00094
00095
00096
00097
00098
00099
00100
00101
00102
00103
00104
00105
00106
00107
00108
00109
00110
00111
00112
00113
00114
00115
00116
00117
00118
00119
00120
00121
00122
00123
00124
00125
00126
00127
00128
00129
00130
00131
00132
00133
00134
00135
00136
00137
00138
00139
00140
00141
00142
00143
00144
00145
00146
00147
00148
00149
00150
00151
00152
00153
00154
00155
00156
00157
00158
00159
00160
00161
00162
00163
00164
00165
00166
00167
00168
00169
00170
00171
00172
00173
00174
00175
00176
00177
00178
00179
00180
00181
00182
00183
00184
00185
00186
00187
00188
00189
00190
00191
00192
00193
00194
00195
00196
00197
00198
00199
00200
00201
00202
00203
00204
00205
00206
00207
00208
00209
00210
00211
00212
00213
00214
00215
00216
00217
00218
00219
00220
00221
00222
00223
00224
00225
00226
00227
00228
00229
00230
00231
00232
00233
00234
00235
00236
00237
00238
00239
00240
00241
00242
00243
00244
00245
00246
00247
00248
00249
00250
00251
00252
00253
00254
00255
00256
00257
00258
00259
00260
00261
00262
00263
00264
00265
00266
00267
00268
00269
00270
00271
00272
00273
00274
00275
00276
00277
00278
00279
00280
00281
00282
00283
00284
00285
00286
00287
00288
00289
00290
00291
00292
00293
00294
00295
00296
00297
00298
00299
00300
00301
00302
00303
00304
00305
00306
00307
00308
00309
00310
00311
00312
00313
00314
00315
00316
00317
00318
00319
00320
00321
00322
00323
00324
00325
00326
00327
00328
00329
00330
00331
00332
00333
00334
00335
00336
00337
00338
00339
00340
00341
00342
00343
00344
00345
00346
00347
00348
00349
00350
00351
00352
00353
00354
00355
00356
00357
00358
00359
00360
00361
00362
00363
00364
00365
00366
00367
00368
00369
00370
00371
00372
00373
00374
00375
00376
00377
00378
00379
00380
00381
00382
00383
00384
00385
00386
00387
00388
00389
00390
00391
00392
00393
00394
00395
00396
00397
00398
00399
00400
00401
00402
00403
00404
00405
00406
00407
00408
00409
00410
00411
00412
00413
00414
00415
00416
00417
00418
00419
00420
00421
00422
00423
00424
00425
00426
00427
00428
00429
00430
00431
00432
00433
00434
00435
00436
00437
00438
00439
00440
00441
00442
00443
00444
00445
00446
00447
00448
00449
00450
00451
00452
00453
00454
00455
00456
00457
00458
00459
00460
00461
00462
00463
00464
00465
00466
00467
00468
00469
00470
00471
00472
00473
00474
00475
00476
00477
00478
00479
00480
00481
00482
00483
00484
00485
00486
00487
00488
00489
00490
00491
00492
00493
00494
00495
00496
00497
00498
00499
00500
00501
00502
00503
00504
00505
00506
00507
00508
00509
00510
00511
00512
00513
00514
00515
00516
00517
00518
00519
00520
00521
00522
00523
00524
00525
00526
00527
00528
00529
00530
00531
00532
00533
00534
00535
00536
00537
00538
00539
00540
00541
00542
00543
00544
00545
00546
00547
00548
00549
00550
00551
00552
00553
00554
00555
00556
00557
00558
00559
00560
00561
00562
00563
00564
00565
00566
00567
00568
00569
00570
00571
00572
00573
00574
00575
00576
00577
00578
00579
00580
00581
00582
00583
00584
00585
00586
00587
00588
00589
00590
00591
00592
00593
00594
00595
00596
00597
00598
00599
00600
00601
00602
00603
00604
00605
00606
00607
00608
00609
00610
00611
00612
00613
00614
00615
00616
00617
00618
00619
00620
00621
00622
00623
00624
00625
00626
00627
00628
00629
00630
00631
00632
00633
00634
00635
00636
00637
00638
00639
00640
00641
00642
00643
00644
00645
00646
00647
00648
00649
00650
00651
00652
00653
00654
00655
00656
00657
00658
00659
00660
00661
00662
00663
00664
00665
00666
00667
00668
00669
00670
00671
00672
00673
00674
00675
00676
00677
00678
00679
00680
00681
00682
00683
00684
00685
00686
00687
00688
00689
00690
00691
00692
00693
00694
00695
00696
00697
00698
00699
00700
00701
00702
00703
00704
00705
00706
00707
00708
00709
00710
00711
00712
00713
00714
00715
00716
00717
00718
00719
00720
00721
00722
00723
00724
00725
00726
00727
00728
00729
00730
00731
00732
00733
00734
00735
00736
00737
00738
00739
00740
00741
00742
00743
00744
00745
00746
00747
00748
00749
00750
00751
00752
00753
00754
00755
00756
00757
00758
00759
00760
00761
00762
00763
00764
00765
00766
00767
00768
00769
00770
00771
00772
00773
00774
00775
00776
00777
00778
00779
00780
00781
00782
00783
00784
00785
00786
00787
00788
00789
00790
00791
00792
00793
00794
00795
00796
00797
00798
00799
00800
00801
00802
00803
00804
00805
00806
00807
00808
00809
00810
00811
00812
00813
00814
00815
00816
00817
00818
00819
00820
00821
00822
00823
00824
00825
00826
00827
00828
00829
00830
00831
00832
00833
00834
00835
00836
00837
00838
00839
00840
00841
00842
00843
00844
00845
00846
00847
00848
00849
00850
00851
00852
00853
00854
00855
00856
00857
00858
00859
00860
00861
00862
00863
00864
00865
00866
00867
00868
00869
00870
00871
00872
00873
00874
00875
00876
00877
00878
00879
00880
00881
00882
00883
00884
00885
00886
00887
00888
00889
00890
00891
00892
00893
00894
00895
00896
00897
00898
00899
00900
00901
00902
00903
00904
00905
00906
00907
00908
00909
00910
00911
00912
00913
00914
00915
00916
00917
00918
00919
00920
00921
00922
00923
00924
00925
00926
00927
00928
00929
00930
00931
00932
00933
00934
00935
00936
00937
00938
00939
00940
00941
00942
00943
00944
00945
00946
00947
00948
00949
00950
00951
00952
00953
00954
00955
00956
00957
00958
00959
00960
00961
00962
00963
00964
00965
00966
00967
00968
00969
00970
00971
00972
00973
00974
00975
00976
00977
00978
00979
00980
00981
00982
00983
00984
00985
00986
00987
00988
00989
00990
00991
00992
00993
00994
00995
00996
00997
00998
00999

```

```

00138 {
00139     return l4vbus_pciroot_cfg_read(bus_cap().cap(), _dev, trigger, polarity);
00140 }
00141
00142 };
00143
00144 }

```

## 16.677 vbus\_pci-ops.h

```

00001 /*
00002  * (c) 2014 Sarah Hoffmann <sarah.hoffmann@kernkonzept.com>
00003  *
00004  * License: see LICENSE.spdx (in this directory or the directories above)
00005  */
00006 #pragma once
00007
00008 #include <l4/vbus/vbus_interfaces.h>
00009
00010 enum
00011 {
00012     L4vbus_pciroot_cfg_read = L4VBUS_INTERFACE_PCI « L4VBUS_IFACE_SHIFT,
00013     L4vbus_pciroot_cfg_write,
00014     L4vbus_pciroot_cfg_irq_enable
00015 };
00016
00017 enum
00018 {
00019     L4vbus_pciroot_cfg_read = L4VBUS_INTERFACE_PCIRoot « L4VBUS_IFACE_SHIFT,
00020     L4vbus_pciroot_cfg_write,
00021     L4vbus_pciroot_cfg_irq_enable
00022 };

```

## 16.678 vbus\_pci.h

```

00001 /*
00002  * (c) 2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00003  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00004  *      economic rights: Technische Universität Dresden (Germany)
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00008 #pragma once
00009
00010 #include <l4/sys/compiler.h>
00011 #include <l4/vbus/vbus_types.h>
00012 #include <l4/sys/types.h>
00013
00014
00015
00016
00017
00018
00019
00020
00021 L4_BEGIN_DECLS
00022
00023 int L4_CV
00024 l4vbus_pci_cfg_read(l4_cap_idx_t vbus, l4vbus_device_handle_t handle,
00025                    l4_uint32_t bus, l4_uint32_t devfn,
00026                    l4_uint32_t reg, l4_uint32_t *value, l4_uint32_t width);
00027
00028 int L4_CV
00029 l4vbus_pci_cfg_write(l4_cap_idx_t vbus, l4vbus_device_handle_t handle,
00030                     l4_uint32_t bus, l4_uint32_t devfn,
00031                     l4_uint32_t reg, l4_uint32_t value, l4_uint32_t width);
00032
00033 int L4_CV
00034 l4vbus_pci_irq_enable(l4_cap_idx_t vbus, l4vbus_device_handle_t handle,
00035                      l4_uint32_t bus, l4_uint32_t devfn,
00036                      int pin, unsigned char *trigger,
00037                      unsigned char *polarity);
00038
00039 int L4_CV
00040 l4vbus_pciroot_cfg_read(l4_cap_idx_t vbus, l4vbus_device_handle_t handle,
00041                         l4_uint32_t reg, l4_uint32_t *value, l4_uint32_t width);
00042
00043 int L4_CV
00044 l4vbus_pciroot_cfg_write(l4_cap_idx_t vbus, l4vbus_device_handle_t handle,
00045                          l4_uint32_t reg, l4_uint32_t value, l4_uint32_t width);
00046
00047 int L4_CV

```

```

00085 l4vbus_pcidev_irq_enable(l4_cap_idx_t vbus, l4vbus_device_handle_t handle,
00086                             unsigned char *trigger,
00087                             unsigned char *polarity);
00088
00089
00090
00092 L4_END_DECLS

```

## 16.679 vbus\_pm-ops.h

```

00001 /*
00002  * (c) 2013 Alexander Warg <warg@os.inf.tu-dresden.de>
00003  *      economic rights: Technische Universität Dresden (Germany)
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007
00008 #pragma once
00009
00010 #include "vbus_interfaces.h"
00011
00012 enum L4vbus_pm_op
00013 {
00014     L4VBUS_PM_OP_SUSPEND = L4VBUS_INTERFACE_PM << L4VBUS_IFACE_SHIFT,
00015     L4VBUS_PM_OP_RESUME,
00016 };
00017

```

## 16.680 vbus\_pm.h

```

00001 /*
00002  * (c) 2013 Alexander Warg <warg@os.inf.tu-dresden.de>
00003  *      economic rights: Technische Universität Dresden (Germany)
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00007 #pragma once
00008
00009 #include <l4/sys/compiler.h>
00010 #include <l4/vbus/vbus_types.h>
00011 #include <l4/sys/types.h>
00012
00018
00019 L4_BEGIN_DECLS
00020
00027 int L4_CV
00028 l4vbus_pm_suspend(l4_cap_idx_t vbus, l4vbus_device_handle_t handle);
00029
00036 int L4_CV
00037 l4vbus_pm_resume(l4_cap_idx_t vbus, l4vbus_device_handle_t handle);
00038
00040
00041 L4_END_DECLS

```


## 16.681 l4/vbus/vbus\_types.h File Reference

This header file contains descriptions of vbus related data types and constants.




```
#include <l4/sys/types.h>
```

Include dependency graph for vbus\_types.h:



This graph shows which files directly or indirectly include this file:



## Data Structures

- struct `l4vbus_resource_t`  
Description of a single vbus resource.
- struct `l4vbus_device_t`  
Detailed information about a vbus device.

## Typedefs

- typedef `l4_mword_t l4vbus_device_handle_t`  
Device handle for a device on the vbus.
- typedef `l4_addr_t l4vbus_paddr_t`  
Address of resources on the vbus.

## Enumerations

- enum [l4vbus\\_resource\\_type\\_t](#) {  
[L4VBUS\\_RESOURCE\\_INVALID](#) = 0 , [L4VBUS\\_RESOURCE\\_IRQ](#) , [L4VBUS\\_RESOURCE\\_MEM](#) ,  
[L4VBUS\\_RESOURCE\\_PORT](#) ,  
[L4VBUS\\_RESOURCE\\_BUS](#) , [L4VBUS\\_RESOURCE\\_GPIO](#) , [L4VBUS\\_RESOURCE\\_DMA\\_DOMAIN](#) ,  
[L4VBUS\\_RESOURCE\\_MAX](#) }

*Description of vbus resource types.*

- enum [l4vbus\\_resource\\_flags\\_t](#) {  
[L4VBUS\\_RESOURCE\\_F\\_MEM\\_R](#) = 0x1 , [L4VBUS\\_RESOURCE\\_F\\_MEM\\_W](#) = 0x2 , [L4VBUS\\_RESOURCE\\_F\\_MEM\\_PREFE](#)  
= 0x10 , [L4VBUS\\_RESOURCE\\_F\\_MEM\\_CACHEABLE](#) = 0x20 ,  
[L4VBUS\\_RESOURCE\\_F\\_MEM\\_MMIO\\_READ](#) = 0x2000 , [L4VBUS\\_RESOURCE\\_F\\_MEM\\_MMIO\\_WRITE](#)  
= 0x4000 }

*Description of vbus resource flags.*

- enum [l4vbus\\_device\\_flags\\_t](#) { [L4VBUS\\_DEVICE\\_F\\_CHILDREN](#) = 0x10 }

*Flags describing device properties, see [l4vbus\\_device\\_t](#).*

### 16.681.1 Detailed Description

This header file contains descriptions of vbus related data types and constants.

Definition in file [vbus\\_types.h](#).

### 16.681.2 Enumeration Type Documentation

#### 16.681.2.1 l4vbus\_device\_flags\_t

enum [l4vbus\\_device\\_flags\\_t](#)

Flags describing device properties, see [l4vbus\\_device\\_t](#).

#### Enumerator

<a href="#">L4VBUS_DEVICE_F_CHILDREN</a>	Device has child devices.
--	---------------------------

Definition at line 92 of file [vbus\\_types.h](#).

#### 16.681.2.2 l4vbus\_resource\_flags\_t

enum [l4vbus\\_resource\\_flags\\_t](#)

Description of vbus resource flags.

#### Enumerator

<a href="#">L4VBUS_RESOURCE_F_MEM_R</a>	Memory resource is readable.
---	------------------------------

L4VBUS_RESOURCE_F_MEM_W	Memory resource is writeable.
L4VBUS_RESOURCE_F_MEM_PREFETCHABLE	Memory resource is prefetchable. Clients may map it buffered or non-cached.
L4VBUS_RESOURCE_F_MEM_CACHEABLE	Memory resource is cacheable. This implies that the memory resource is prefetchable. If not set, clients must not map it cached. If the resource is neither cacheable nor prefetchable, clients must map it non-cached!
L4VBUS_RESOURCE_F_MEM_MMIO_READ	Reading needs to be performed using the MMIO space protocol.
L4VBUS_RESOURCE_F_MEM_MMIO_WRITE	Writing needs to be performed using the MMIO space protocol.

Definition at line 51 of file [vbus\\_types.h](#).

### 16.681.2.3 l4vbus\_resource\_type\_t

enum [l4vbus\\_resource\\_type\\_t](#)

Description of vbus resource types.

#### Enumerator

L4VBUS_RESOURCE_INVALID	Invalid type.
L4VBUS_RESOURCE_IRQ	Interrupt resource.
L4VBUS_RESOURCE_MEM	I/O memory resource.
L4VBUS_RESOURCE_PORT	I/O port resource (x86 only).
L4VBUS_RESOURCE_BUS	Bus resource.
L4VBUS_RESOURCE_GPIO	Gpio resource.
L4VBUS_RESOURCE_DMA_DOMAIN	DMA domain.
L4VBUS_RESOURCE_MAX	Maximum resource id.

Definition at line 39 of file [vbus\\_types.h](#).

## 16.682 vbus\_types.h

[Go to the documentation of this file.](#)

```

00001 /*
00002  * (c) 2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00003  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00004  *      economic rights: Technische Universität Dresden (Germany)
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00013 #pragma once
00014
00015 #include <l4/sys/types.h>
00016
00018 typedef l4_mword_t l4vbus_device_handle_t;
00020 typedef l4_addr_t l4vbus_paddr_t;
00021
00023 typedef struct {

```

```

00025  l4_uint16_t    type;
00027  l4_uint16_t    flags;
00029  l4vbus_paddr_t start;
00031  l4vbus_paddr_t end;
00033  l4vbus_device_handle_t provider;
00035  l4_uint32_t id;
00036 } l4vbus_resource_t;
00037
00039 enum l4vbus_resource_type_t {
00040     L4VBUS_RESOURCE_INVALID = 0,
00041     L4VBUS_RESOURCE_IRQ,
00042     L4VBUS_RESOURCE_MEM,
00043     L4VBUS_RESOURCE_PORT,
00044     L4VBUS_RESOURCE_BUS,
00045     L4VBUS_RESOURCE_GPIO,
00046     L4VBUS_RESOURCE_DMA_DOMAIN,
00047     L4VBUS_RESOURCE_MAX,
00048 };
00049
00051 enum l4vbus_resource_flags_t {
00053     L4VBUS_RESOURCE_F_MEM_R = 0x1,
00055     L4VBUS_RESOURCE_F_MEM_W = 0x2,
00060     L4VBUS_RESOURCE_F_MEM_PREFETCHABLE = 0x10,
00067     L4VBUS_RESOURCE_F_MEM_CACHEABLE = 0x20,
00069     L4VBUS_RESOURCE_F_MEM_MMIO_READ = 0x2000,
00071     L4VBUS_RESOURCE_F_MEM_MMIO_WRITE = 0x4000,
00072 };
00073
00074 enum l4vbus_consts_t {
00075     L4VBUS_DEV_NAME_LEN = 64,
00076     L4VBUS_MAX_DEPTH = 100,
00077 };
00078
00080 typedef struct {
00082     l4_uint32_t    type;
00084     char           name[L4VBUS_DEV_NAME_LEN];
00086     unsigned       num_resources;
00088     unsigned       flags;
00089 } l4vbus_device_t;
00090
00092 enum l4vbus_device_flags_t {
00093     L4VBUS_DEVICE_F_CHILDREN = 0x10,
00094 };

```

## 16.683 vdevice-ops.h

```


00001 /*
00002  * (c) 2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00003  *      Alexander Warg <warg@os.inf.tu-dresden.de>,
00004  *      Torsten Frenzel <frenzel@os.inf.tu-dresden.de>
00005  *      economic rights: Technische Universität Dresden (Germany)
00006  *
00007  * License: see LICENSE.spdx (in this directory or the directories above)
00008  */
00009 #pragma once
00010
00011 #include "vbus_interfaces.h"
00012
00013 enum L4vbus_vdevice_op
00014 {
00015     L4vbus_vdevice_hid = L4VBUS_INTERFACE_GENERIC « L4VBUS_IFACE_SHIFT,
00016     L4vbus_vdevice_adr,
00017     L4vbus_vdevice_get_by_hid,
00018     L4vbus_vdevice_get_next,
00019     L4vbus_vdevice_get_resource,
00020     L4vbus_vdevice_get_hid,
00021     L4vbus_vdevice_is_compatible,
00022     L4vbus_vdevice_get,
00023 };
00024
00025 enum {
00026     L4vbus_vbus_request_resource = L4VBUS_INTERFACE_BUS « L4VBUS_IFACE_SHIFT,
00027     L4vbus_vbus_release_resource,
00028     L4vbus_vbus_assign_dma_domain,
00029 };
00030
00031 enum
00032 {
00033     L4vbus_vicu_get_cap = L4VBUS_INTERFACE_ICU « L4VBUS_IFACE_SHIFT
00034 };
00035

```

## 16.684 l4/vcpu/vcpu File Reference

vCPU support library (C++ interface).

```
#include <l4/re/env>
#include <l4/vcpu/vcpu.h>
Include dependency graph for vcpu:
```



### Data Structures

- class [L4vcpu::State](#)  
*C++ implementation of state word in the vCPU area.*
- class [L4vcpu::Vcpu](#)  
*C++ implementation of the vCPU save state area.*

### 16.684.1 Detailed Description

vCPU support library (C++ interface).

Definition in file [vcpu](#).

## 16.685 vcpu

[Go to the documentation of this file.](#)

```
00001 // vi:se ft=cpp:
00002 /*
00003  * (c) 2010 Adam Lackorzynski <adam@os.inf.tu-dresden.de>
00004  *     economic rights: Technische Universität Dresden (Germany)
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00012
00013 #pragma once
00014
00015 #include <l4/re/env>
00016 #include <l4/vcpu/vcpu.h>
00017
00018 namespace L4vcpu {
```

```

00019
00024 class State
00025 {
00026 public:
00027     State() {}
00028
00034     explicit State(unsigned v) : _s(v) {}
00035
00041     void add(unsigned bits) throw() { _s |= bits; }
00042
00048     void clear(unsigned bits) throw() { _s &= ~bits; }
00049
00055     void set(unsigned v) throw() { _s = v; }
00056
00057 private:
00058     __typeof__(((l4_vcpu_state_t *)0)->state) _s;
00059 };
00060
00065 class Vcpu : private l4_vcpu_state_t
00066 {
00067 public:
00071     void irq_disable() throw()
00072     { l4vcpu_irq_disable(this); }
00073
00078     unsigned irq_disable_save() throw()
00079     { return l4vcpu_irq_disable_save(this); }
00080
00081     l4_vcpu_state_t *s() { return this; }
00082     l4_vcpu_state_t const *s() const { return this; }
00083
00088     State *state() throw()
00089     {
00090         static_assert(sizeof(State) == sizeof(l4_vcpu_state_t::state),
00091             "size mismatch");
00092         return reinterpret_cast<State *>(&(l4_vcpu_state_t::state));
00093     }
00094
00099     State state() const throw()
00100     { return static_cast<State>(l4_vcpu_state_t::state); }
00101
00106     State *saved_state() throw()
00107     {
00108         static_assert(sizeof(State) == sizeof(l4_vcpu_state_t::saved_state),
00109             "size mismatch");
00110         return reinterpret_cast<State *>(&(l4_vcpu_state_t::saved_state));
00111     }
00116     State saved_state() const throw()
00117     { return static_cast<State>(l4_vcpu_state_t::saved_state); }
00118
00122     l4_uint16_t sticky_flags() const throw()
00123     { return l4_vcpu_state_t::sticky_flags; }
00124
00135     void irq_enable(l4_utcb_t *utcb, l4vcpu_event_hndl_t do_event_work_cb,
00136         l4vcpu_setup_ipc_t setup_ipc) throw()
00137     { l4vcpu_irq_enable(this, utcb, do_event_work_cb, setup_ipc); }
00138
00150     void irq_restore(unsigned s, l4_utcb_t *utcb,
00151         l4vcpu_event_hndl_t do_event_work_cb,
00152         l4vcpu_setup_ipc_t setup_ipc) throw()
00153     { l4vcpu_irq_restore(this, s, utcb, do_event_work_cb, setup_ipc); }
00154
00166     void wait_for_event(l4_utcb_t *utcb, l4vcpu_event_hndl_t do_event_work_cb,
00167         l4vcpu_setup_ipc_t setup_ipc) throw()
00168     { l4vcpu_wait_for_event(this, utcb, do_event_work_cb, setup_ipc); }
00169
00174     void task(L4::Cap<L4::Task> const task = L4::Cap<L4::Task>::Invalid) throw()
00175     { user_task = task.cap(); }
00176
00181     int is_page_fault_entry() const
00182     { return l4vcpu_is_page_fault_entry(this); }
00183
00188     int is_irq_entry() const
00189     { return l4vcpu_is_irq_entry(this); }
00190
00195     l4_vcpu_regs_t *r() throw()
00196     { return &(l4_vcpu_state_t::r); }
00197
00202     l4_vcpu_regs_t const *r() const throw()
00203     { return &(l4_vcpu_state_t::r); }
00204
00209     l4_vcpu_ipc_regs_t *i() throw()
00210     { return &(l4_vcpu_state_t::i); }
00211
00216     l4_vcpu_ipc_regs_t const *i() const throw()
00217     { return &(l4_vcpu_state_t::i); }
00218
00225     void entry_sp(l4_umword_t sp)

```

```

00226 { l4_vcpu_state_t::entry_sp = sp; }
00227
00232 void entry_ip(l4_umword_t ip)
00233 { l4_vcpu_state_t::entry_ip = ip; }
00234
00246 L4_CV static int
00247 ext_alloc(Vcpu **vcpu,
00248           l4_addr_t *ext_state,
00249           L4::Cap<L4::Task> task = L4Re::Env::env()->task(),
00250           L4::Cap<L4Re::Rm> rm = L4Re::Env::env()->rm()) throw();
00251
00259 static inline Vcpu *cast(void *x) throw()
00260 { return reinterpret_cast<Vcpu *>(x); }
00261
00269 static inline Vcpu *cast(l4_addr_t x) throw()
00270 { return reinterpret_cast<Vcpu *>(x); }
00271
00275 void print_state(const char *prefix = "") const throw()
00276 { l4vcpu_print_state(this, prefix); }
00277 };
00278
00279
00280 }

```

## 16.686 l4/sys/vcpu.h File Reference


### vCPU API

```


#include <l4/sys/types.h>
#include <l4/sys/__vcpu-arch.h>

```

Include dependency graph for vcpu.h:



This graph shows which files directly or indirectly include this file:



## Data Structures

- struct [l4\\_vcpu\\_state\\_t](#)  
*State of a vCPU.*

## Typedefs

- typedef struct [l4\\_vcpu\\_state\\_t](#) **[l4\\_vcpu\\_state\\_t](#)**  
*State of a vCPU.*

## Enumerations

- enum [L4\\_vcpu\\_state\\_flags](#) {  
[L4\\_VCPU\\_F\\_IRQ](#) = 0x01 , [L4\\_VCPU\\_F\\_PAGE\\_FAULTS](#) = 0x02 , [L4\\_VCPU\\_F\\_EXCEPTIONS](#) = 0x04 ,  
[L4\\_VCPU\\_F\\_USER\\_MODE](#) = 0x20 ,  
[L4\\_VCPU\\_F\\_FPU\\_ENABLED](#) = 0x80 }  
*State flags of a vCPU.*
- enum [L4\\_vcpu\\_sticky\\_flags](#) { [L4\\_VCPU\\_SF\\_IRQ\\_PENDING](#) = 0x01 }  
*Sticky flags of a vCPU.*

## Functions

- int [l4\\_vcpu\\_check\\_version](#) ([l4\\_vcpu\\_state\\_t](#) const \*vcpu) [L4\\_NOTHROW](#)  
*Check if a vCPU state has the right version.*

## 16.686.1 Detailed Description

vCPU API

Definition in file [vcpu.h](#).



## 16.686.2 Function Documentation

### 16.686.2.1 l4\_vcpu\_check\_version()

```
int l4_vcpu_check_version (
    l4_vcpu_state_t const * vcpu) [inline]
```

Check if a vCPU state has the right version.

#### Parameters

<i>vcpu</i>	A pointer to an initialized vCPU state.
-------------	---

#### Return values

1	If the vCPU state has a matching version ID for the current vCPU user-level structures.
0	If the vCPU state has a different (incompatible) version ID than the current vCPU user-level structures.

Definition at line 191 of file [vcpu.h](#).

References [L4\\_NOTHROW](#), and [L4\\_VCPU\\_STATE\\_VERSION](#).

## 16.687 vcpu.h

[Go to the documentation of this file.](#)

```
00001 /*
00002  * (c) 2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
00003  *      Alexander Warg <warg@os.inf.tu-dresden.de>
00004  *      economic rights: Technische Universität Dresden (Germany)
00005  *
00006  * License: see LICENSE.spdx (in this directory or the directories above)
00007  */
00012 #pragma once
00013
00014 #include <l4/sys/types.h>
00015 #include <l4/sys/__vcpu-arch.h>
00016
00070
00075 typedef struct l4_vcpu_state_t
00076 {
00077     l4_umword_t      version;
00080     l4_umword_t      user_data[7];
00081     l4_vcpu_regs_t   r;
00082     l4_vcpu_ipc_regs_t i;
00083
00084     l4_uint16_t      state;
00085     l4_uint16_t      saved_state;
00086     l4_uint16_t      sticky_flags;
00087     l4_uint16_t      _reserved;
00088
00089     l4_cap_idx_t      user_task;
00090
00091     l4_umword_t      entry_sp;
00092     l4_umword_t      entry_ip;
00093     l4_umword_t      reserved_sp;
00094     l4_vcpu_arch_state_t arch_state;
00095 } l4_vcpu_state_t;
00096
00101 enum L4_vcpu_state_flags
00102 {
00114     L4_VCPU_F_IRQ          = 0x01,
00115
00129     L4_VCPU_F_PAGE_FAULTS = 0x02,
```

```

00130
00142  L4_VCPU_F_EXCEPTIONS  = 0x04,
00143
00152  L4_VCPU_F_USER_MODE   = 0x20,
00153
00160  L4_VCPU_F_FPU_ENABLED = 0x80,
00161 };
00162
00167 enum L4_vcpu_sticky_flags
00168 {
00171  L4_VCPU_SF_IRQ_PENDING = 0x01,
00172 };
00173
00185 L4_INLINE int
00186 l4_vcpu_check_version(l4_vcpu_state_t const *vcpu) L4_NOTHROW;
00187
00188 /* IMPLEMENTATION: ----- */
00189
00190 L4_INLINE int
00191 l4_vcpu_check_version(l4_vcpu_state_t const *vcpu) L4_NOTHROW
00192 {
00193     return vcpu->version == L4_VCPU_STATE_VERSION;
00194 }

```

## 16.688 I4/vcpu/vcpu.h File Reference


vCPU support library (C interface).

```


#include <l4/sys/vcpu.h>
#include <l4/sys/utcb.h>
#include <l4/sys/ipc.h>
#include <l4/vcpu/vcpu_arch.h>

```

Include dependency graph for vcpu.h:



This graph shows which files directly or indirectly include this file:



## Functions

- void [l4vcpu\\_irq\\_disable](#) ([l4\\_vcpu\\_state\\_t](#) \*vcpu) [L4\\_NOTHROW](#)  
*Disable a vCPU for event delivery.*
- unsigned [l4vcpu\\_irq\\_disable\\_save](#) ([l4\\_vcpu\\_state\\_t](#) \*vcpu) [L4\\_NOTHROW](#)  
*Disable a vCPU for event delivery and return previous state.*
- void [l4vcpu\\_irq\\_enable](#) ([l4\\_vcpu\\_state\\_t](#) \*vcpu, [l4\\_utcb\\_t](#) \*utcb, [l4vcpu\\_event\\_hndl\\_t](#) do\_event\_work\_cb, [l4vcpu\\_setup\\_ipc\\_t](#) setup\_ipc) [L4\\_NOTHROW](#)  
*Enable a vCPU for event delivery.*
- void [l4vcpu\\_irq\\_restore](#) ([l4\\_vcpu\\_state\\_t](#) \*vcpu, unsigned s, [l4\\_utcb\\_t](#) \*utcb, [l4vcpu\\_event\\_hndl\\_t](#) do\_event\_work\_cb, [l4vcpu\\_setup\\_ipc\\_t](#) setup\_ipc) [L4\\_NOTHROW](#)  
*Restore a previously saved IRQ/event state.*
- void [l4vcpu\\_wait\\_for\\_event](#) ([l4\\_vcpu\\_state\\_t](#) \*vcpu, [l4\\_utcb\\_t](#) \*utcb, [l4vcpu\\_event\\_hndl\\_t](#) do\_event\_work\_cb, [l4vcpu\\_setup\\_ipc\\_t](#) setup\_ipc) [L4\\_NOTHROW](#)  
*Wait for event.*
- void [l4vcpu\\_print\\_state](#) (const [l4\\_vcpu\\_state\\_t](#) \*vcpu, const char \*prefix) [L4\\_NOTHROW](#)  
*Print the state of a vCPU.*
- int [l4vcpu\\_is\\_irq\\_entry](#) ([l4\\_vcpu\\_state\\_t](#) const \*vcpu) [L4\\_NOTHROW](#)  
*Return whether the entry reason was an IRQ/IPC message.*
- int [l4vcpu\\_is\\_page\\_fault\\_entry](#) ([l4\\_vcpu\\_state\\_t](#) const \*vcpu) [L4\\_NOTHROW](#)  
*Return whether the entry reason was a page fault.*
- int [l4vcpu\\_ext\\_alloc](#) ([l4\\_vcpu\\_state\\_t](#) \*\*vcpu, [l4\\_addr\\_t](#) \*ext\_state, [l4\\_cap\\_idx\\_t](#) task, [l4\\_cap\\_idx\\_t](#) regmgr) [L4\\_NOTHROW](#)  
*Allocate state area for an extended vCPU.*

### 16.688.1 Detailed Description

vCPU support library (C interface).

Definition in file [vcpu.h](#).

## 16.689 vcpu.h

[Go to the documentation of this file.](#)

```

00001 /*
00002  * (c) 2010 Adam Lackorzynski <adam@os.inf.tu-dresden.de>
00003  *      economic rights: Technische Universität Dresden (Germany)
00004  *
00005  * License: see LICENSE.spdx (in this directory or the directories above)
00006  */
00011 #pragma once
00012
00013 #include <l4/sys/vcpu.h>
00014 #include <l4/sys/utcb.h>
00015
00016 __BEGIN_DECLS
00017
00026
00032
00033 typedef void (*l4vcpu_event_hndl_t) (l4_vcpu_state_t *vcpu);
00034 typedef void (*l4vcpu_setup_ipc_t) (l4_utcb_t *utcb);
00035
00042 L4_CV L4_INLINE
00043 void
00044 l4vcpu_irq_disable(l4_vcpu_state_t *vcpu) L4_NOTHROW;
00045
00054 L4_CV L4_INLINE
00055 unsigned
00056 l4vcpu_irq_disable_save(l4_vcpu_state_t *vcpu) L4_NOTHROW;
00057
00070 L4_CV L4_INLINE
00071 void
00072 l4vcpu_irq_enable(l4_vcpu_state_t *vcpu, l4_utcb_t *utcb,
00073                  l4vcpu_event_hndl_t do_event_work_cb,
00074                  l4vcpu_setup_ipc_t setup_ipc) L4_NOTHROW;
00075
00090 L4_CV L4_INLINE
00091 void
00092 l4vcpu_irq_restore(l4_vcpu_state_t *vcpu, unsigned s,
00093                   l4_utcb_t *utcb,
00094                   l4vcpu_event_hndl_t do_event_work_cb,
00095                   l4vcpu_setup_ipc_t setup_ipc) L4_NOTHROW;
00096
00110 L4_CV L4_INLINE
00111 void
00112 l4vcpu_wait(l4_vcpu_state_t *vcpu, l4_utcb_t *utcb,
00113             l4_timeout_t to,
00114             l4vcpu_event_hndl_t do_event_work_cb,
00115             l4vcpu_setup_ipc_t setup_ipc) L4_NOTHROW;
00116
00130 L4_CV L4_INLINE
00131 void
00132 l4vcpu_wait_for_event(l4_vcpu_state_t *vcpu, l4_utcb_t *utcb,
00133                      l4vcpu_event_hndl_t do_event_work_cb,
00134                      l4vcpu_setup_ipc_t setup_ipc) L4_NOTHROW;
00135
00136
00144 L4_CV void
00145 l4vcpu_print_state(const l4_vcpu_state_t *vcpu, const char *prefix) L4_NOTHROW;
00146
00150 L4_CV void
00151 l4vcpu_print_state_arch(const l4_vcpu_state_t *vcpu, const char *prefix) L4_NOTHROW;
00152
00153
00162 L4_CV L4_INLINE
00163 int
00164 l4vcpu_is_irq_entry(l4_vcpu_state_t const *vcpu) L4_NOTHROW;
00165
00174 L4_CV L4_INLINE
00175 int
00176 l4vcpu_is_page_fault_entry(l4_vcpu_state_t const *vcpu) L4_NOTHROW;
00177
00189 L4_CV int
00190 l4vcpu_ext_alloc(l4_vcpu_state_t **vcpu, l4_addr_t *ext_state,
00191                 l4_cap_idx_t task, l4_cap_idx_t regmgr) L4_NOTHROW;
00192
00193 /* ===== */
00194 /* Implementations */
00195
00196 #include <l4/sys/ipc.h>
00197 #include <l4/vcpu/vcpu_arch.h>
00198
00199 L4_CV L4_INLINE
00200 void
00201 l4vcpu_irq_disable(l4_vcpu_state_t *vcpu) L4_NOTHROW
00202 {

```

```

00203     vcpu->state &= ~L4_VCPU_F_IRQ;
00204     l4_barrier();
00205 }
00206
00207 L4_CV L4_INLINE
00208 unsigned
00209 l4vcpu_irq_disable_save(l4_vcpu_state_t *vcpu) L4_NOTHROW
00210 {
00211     unsigned s = vcpu->state;
00212     l4vcpu_irq_disable(vcpu);
00213     return s;
00214 }
00215
00216 L4_CV L4_INLINE
00217 void
00218 l4vcpu_wait(l4_vcpu_state_t *vcpu, l4_utcb_t *utcb,
00219             l4_timeout_t to,
00220             l4vcpu_event_hndl_t do_event_work_cb,
00221             l4vcpu_setup_ipc_t setup_ipc) L4_NOTHROW
00222 {
00223     l4vcpu_irq_disable(vcpu);
00224     setup_ipc(utcb);
00225     vcpu->i.tag = l4_ipc_wait(utcb, &vcpu->i.label, to);
00226     if (L4_LIKELY(!l4_msgtag_has_error(vcpu->i.tag)))
00227         do_event_work_cb(vcpu);
00228 }
00229
00230 L4_CV L4_INLINE
00231 void
00232 l4vcpu_irq_enable(l4_vcpu_state_t *vcpu, l4_utcb_t *utcb,
00233                  l4vcpu_event_hndl_t do_event_work_cb,
00234                  l4vcpu_setup_ipc_t setup_ipc) L4_NOTHROW
00235 {
00236     if (!(vcpu->state & L4_VCPU_F_IRQ))
00237     {
00238         setup_ipc(utcb);
00239         l4_barrier();
00240     }
00241
00242     while (1)
00243     {
00244         vcpu->state |= L4_VCPU_F_IRQ;
00245         l4_barrier();
00246
00247         if (L4_LIKELY(!(vcpu->sticky_flags & L4_VCPU_SF_IRQ_PENDING)))
00248             break;
00249
00250         l4vcpu_wait(vcpu, utcb, L4_IPC_BOTH_TIMEOUT_0,
00251                     do_event_work_cb, setup_ipc);
00252     }
00253 }
00254
00255 L4_CV L4_INLINE
00256 void
00257 l4vcpu_irq_restore(l4_vcpu_state_t *vcpu, unsigned s,
00258                   l4_utcb_t *utcb,
00259                   l4vcpu_event_hndl_t do_event_work_cb,
00260                   l4vcpu_setup_ipc_t setup_ipc) L4_NOTHROW
00261 {
00262     if (s & L4_VCPU_F_IRQ)
00263         l4vcpu_irq_enable(vcpu, utcb, do_event_work_cb, setup_ipc);
00264     else if (vcpu->state & L4_VCPU_F_IRQ)
00265         l4vcpu_irq_disable(vcpu);
00266 }
00267
00268 L4_CV L4_INLINE
00269 void
00270 l4vcpu_wait_for_event(l4_vcpu_state_t *vcpu, l4_utcb_t *utcb,
00271                      l4vcpu_event_hndl_t do_event_work_cb,
00272                      l4vcpu_setup_ipc_t setup_ipc) L4_NOTHROW
00273 {
00274     l4vcpu_wait(vcpu, utcb, L4_IPC_NEVER, do_event_work_cb, setup_ipc);
00275 }
00276
00277 __END_DECLS

```



# Chapter 17

## Examples

### 17.1 hello/server/src/main.c

This is the famous "Hello World!" program.

This is the famous "Hello World!" program.

```
/* SPDX-License-Identifier: MIT */

#include <stdio.h>
#include <unistd.h>

int main(void)
{
    for (;;)
    {
        puts("Hello World!");
        sleep(1);
    }
}
```

### 17.2 examples/sys/ipc/ipc\_example.c

This example shows how two threads can exchange data using the [L4](#) IPC mechanism.

This example shows how two threads can exchange data using the [L4](#) IPC mechanism. One thread is sending an integer to the other thread which is returning the square of the integer. Both values are printed.

```
/* SPDX-License-Identifier: MIT */
/*
 * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>
 */
#include <pthread-l4.h>
#include <unistd.h>
#include <stdio.h>

#include <l4/sys/ipc.h>

static pthread_t t2;

/* Thread1 is the initiator thread, i.e. it initiates the IPC calls. In
 * other words, it takes the client role. It uses L4 IPC mechanisms to send
 * an integer value to thread2 and received a calculation result back. */
static void *thread1_fn(void *arg)
{
    l4_msgtag_t tag;
    int ipc_error;
    unsigned long value = 1;
    (void)arg;

    while (1)
```

```

{
    printf("Sending: %ld\n", value);

    /* Store the value which we want to have squared in the first message
     * register of our UTCB. */
    l4_utcb_mr()->mr[0] = value;

    /* To an L4 IPC call, i.e. send a message to thread2 and wait for a
     * reply from thread2. The '1' in the msgtag denotes that we want to
     * transfer one word of our message registers (i.e. MR0). No timeout. */
    tag = l4_ipc_call(pthread_l4_cap(t2), l4_utcb(),
                     l4_msgtag(0, 1, 0, 0), L4_IPC_NEVER);
    /* Check for IPC error, if yes, print out the IPC error code, if not,
     * print the received result. */
    ipc_error = l4_ipc_error(tag, l4_utcb());
    if (ipc_error)
        fprintf(stderr, "thread1: IPC error: %x\n", ipc_error);
    else
        printf("Received: %ld\n", l4_utcb_mr()->mr[0]);

    /* Wait some time and increment our value. */
    sleep(1);
    value++;
}
return NULL;
}

/* Thread2 is in the server role, i.e. it waits for requests from others and
 * sends back the calculation results. */
static void *thread2_fn(void *arg)
{
    l4_msgtag_t tag;
    l4_umword_t label;
    int ipc_error;
    (void)arg;

    /* Wait for requests from any thread. No timeout, i.e. wait forever. */
    tag = l4_ipc_wait(l4_utcb(), &label, L4_IPC_NEVER);
    while (1)
    {
        /* Check if we had any IPC failure, if yes, print the error code
         * and just wait again. */
        ipc_error = l4_ipc_error(tag, l4_utcb());
        if (ipc_error)
        {
            fprintf(stderr, "thread2: IPC error: %x\n", ipc_error);
            tag = l4_ipc_wait(l4_utcb(), &label, L4_IPC_NEVER);
            continue;
        }

        /* So, the IPC was ok, now take the value out of message register 0
         * of the UTCB and store the square of it back to it. */
        l4_utcb_mr()->mr[0] = l4_utcb_mr()->mr[0] * l4_utcb_mr()->mr[0];

        /* Send the reply and wait again for new messages.
         * The '1' in the msgtag indicated that we want to transfer 1 word in
         * the message registers (i.e. MR0) */
        tag = l4_ipc_reply_and_wait(l4_utcb(), l4_msgtag(0, 1, 0, 0),
                                   &label, L4_IPC_NEVER);
    }
    return NULL;
}

int main(void)
{
    // We will have two threads, one is already running the main function, the
    // other (thread2) will be created using pthread_create.

    if (pthread_create(&t2, NULL, thread2_fn, NULL))
    {
        fprintf(stderr, "Thread creation failed\n");
        return 1;
    }

    // Just run thread1 in the main thread
    thread1_fn(NULL);
    return 0;
}

```

## 17.3 examples/sys/ipc/ipc.cfg

Sample configuration file for the IPC example.



Sample configuration file for the IPC example.

```
# vim:se ft=lua:

local L4 = require("L4");

L4.default_loader:start({}, "rom/ex_ipc1");
```

## 17.4 examples/sys/start-with-exc/main.c

This example shows how to start a newly created thread with a defined set of CPU registers.

This example shows how to start a newly created thread with a defined set of CPU registers.

```
/* SPDX-License-Identifier: MIT */
/*
 * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
 *               Alexander Warg <warg@os.inf.tu-dresden.de>,
 *               Björn Döbel <doebel@os.inf.tu-dresden.de>,
 *               Frank Mehnert <fm3@os.inf.tu-dresden.de>
 */
/*
 * Start a thread with an exception reply. This example does only work on
 * the x86-32 and ARM architectures.
 */

#include <l4/sys/thread.h>
#include <l4/sys/factory.h>
#include <l4/sys/ipc.h>
#include <l4/sys/scheduler.h>
#include <l4/sys/utcb.h>
#include <l4/util/util.h>
#include <l4/re/env.h>
#include <l4/re/c/util/cap_alloc.h>

#include <stdlib.h>
#include <stdio.h>

/* Stack for the thread to be created. 8kB are enough. */
static char thread_stack[8 « 10];

/* The thread to be created. For illustration it will print out its
 * register set.
 */
static void L4_STICKY(thread_func(l4_umword_t *d))
{
    while (1)
    {
        printf("hey, I'm a thread\n");
        printf("got register values: %ld %ld %ld %ld %ld %ld %ld %ld\n",
              d[7], d[6], d[5], d[4], d[2], d[1], d[0]);
        l4_sleep(800);
    }
}

/* Startup trick for this example. Put all the CPU registers on the stack so
 * that the C function above can get it on the stack. */
asm(
    ".global thread      \n"
    "thread:             \n"
    #ifdef ARCH_x86
    "    pusha            \n"
    "    push %esp        \n"
    "    call thread_func \n"
    #endif
    #ifdef ARCH_arm
    "    push {r0-r7}     \n"
    "    mov r0, sp        \n"
    "    bl thread_func   \n"
    #endif
    #ifdef ARCH_arm64
    "    stp x0, x1, [sp, #0]! \n"
    "    stp x2, x3, [sp, #0]! \n"
    "    stp x4, x5, [sp, #0]! \n"
    "    stp x6, x7, [sp, #0]! \n"
    "    mov x0, sp        \n"
    "    bl thread_func     \n"
    #endif
);
extern void thread(void);

/* Our main function */
```

```

int main(void)
{
    /* Get a capability slot for our new thread. */
    l4_cap_idx_t t1 = l4re_util_cap_alloc();
    l4_utcb_t *u = l4_utcb();
    l4_exc_regs_t *e = l4_utcb_exc_u(u);
    l4_msgtag_t tag;
    int err;

    printf("Example showing how to start a thread with an exception.\n");
    /* We do not want to implement a pager here, take the shortcut. */
    printf("Make sure to start this program with ldr-flags=eager_map\n");

    if (l4_is_invalid_cap(t1))
        return 1;

    /* Create the thread using our default factory */
    tag = l4_factory_create_thread(l4re_env()->factory, t1);
    if (l4_error(tag))
        return 1;

    /* Setup the thread by setting the pager and task. */
    l4_thread_control_start();
    l4_thread_control_pager(l4re_env()->main_thread);
    l4_thread_control_exc_handler(l4re_env()->main_thread);
    l4_thread_control_bind((l4_utcb_t *)l4re_env()->first_free_utcb,
                          L4RE_THIS_TASK_CAP);
    tag = l4_thread_control_commit(t1);
    if (l4_error(tag))
        return 2;

    /* Start the thread by finally setting instruction and stack pointer */
    tag = l4_thread_ex_regs(t1,
                           (l4_umword_t)thread,
                           (l4_umword_t)thread_stack + sizeof(thread_stack),
                           L4_THREAD_EX_REGS_TRIGGER_EXCEPTION);

    if (l4_error(tag))
        return 3;

    l4_sched_param_t sp = l4_sched_param(1, 0);
    tag = l4_scheduler_run_thread(l4re_env()->scheduler, t1, &sp);
    if (l4_error(tag))
        return 4;

    /* Receive initial exception from just started thread */
    tag = l4_ipc_receive(t1, u, L4_IPC_NEVER);
    if ((err = l4_ipc_error(tag, u)))
    {
        printf("Umm, ipc error: %x\n", err);
        return 1;
    }
    /* We expect an exception IPC */
    if (!l4_msgtag_is_exception(tag))
    {
        printf("PF?: %lx %lx (not prepared to handle this) %ld\n",
              l4_utcb_mr_u(u)->mr[0], l4_utcb_mr_u(u)->mr[1], l4_msgtag_label(tag));
        return 1;
    }

    /* Fill out the complete register set of the new thread */
    e->sp = (l4_umword_t)(thread_stack + sizeof(thread_stack));
#ifdef ARCH_x86
    e->ip = (l4_umword_t)thread;
    e->edi = 0;
    e->esi = 1;
    e->ebp = 2;
    e->ebx = 4;
    e->edx = 5;
    e->ecx = 6;
    e->eax = 7;
#endif
#ifdef ARCH_arm
    e->pc = (l4_umword_t)thread;
    e->r[0] = 0;
    e->r[1] = 1;
    e->r[2] = 2;
    e->r[3] = 3;
    e->r[4] = 4;
    e->r[5] = 5;
    e->r[6] = 6;
    e->r[7] = 7;
#endif
#ifdef ARCH_arm64
    e->pc = (l4_umword_t)thread;
    e->r[0] = 0;
    e->r[1] = 1;

```

```

e->r[2] = 2;
e->r[3] = 3;
e->r[4] = 4;
e->r[5] = 5;
e->r[6] = 6;
e->r[7] = 7;
#endif
/* Send a complete exception */
tag = l4_msgtag(0, L4_UTCB_EXCEPTION_REGS_SIZE, 0, 0);

/* Send reply and start the thread with the defined CPU register set */
tag = l4_ipc_send(tl, u, tag, L4_IPC_NEVER);
if ((err = l4_ipc_error(tag, u)))
    printf("Error sending IPC: %x\n", err);

/* Idle around */
while (1)
    l4_sleep(10000);

return 0;
}

```

## 17.5 examples/sys/singlestep/main.c

This example shows how a thread can be single stepped on the x86 architecture.

This example shows how a thread can be single stepped on the x86 architecture.

```

/* SPDX-License-Identifier: MIT */
/*
 * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
 *             Alexander Warg <warg@os.inf.tu-dresden.de>,
 *             Björn Döbel <doebel@os.inf.tu-dresden.de>
 */
/*
 * Single stepping example for the x86-32 architecture.
 */
#include <l4/sys/ipc.h>
#include <l4/sys/factory.h>
#include <l4/sys/thread.h>
#include <l4/sys/scheduler.h>
#include <l4/sys/utcb.h>
#include <l4/sys/kdebug.h>

#include <l4/util/util.h>
#include <l4/re/env.h>
#include <l4/re/c/util/cap_alloc.h>

#include <stdlib.h>
#include <stdio.h>
#include <string.h>

static char thread_stack[8 « 10];

static void thread_func(void)
{
    while (1)
    {
        unsigned long d = 0;

        /* Enable single stepping */
        asm volatile("pushf; pop %0; or $256,%0; push %0; popf\n"
                     : "=r" (d) : "r" (d));

        /* Some instructions */
        asm volatile("nop");
        asm volatile("nop");
        asm volatile("nop");
        asm volatile("mov $0x12345000, %%edx" : : : "edx"); // a non-existent cap
        asm volatile("int $0x30\n");
        asm volatile("nop");
        asm volatile("nop");
        asm volatile("nop");

        /* Disabled single stepping */
        asm volatile("pushf; pop %0; and $~256,%0; push %0; popf\n"
                     : "=r" (d) : "r" (d));

        /* You won't see those */
        asm volatile("nop");
        asm volatile("nop");
    }
}

```

```

        asm volatile("nop");
    }
}

int main(void)
{
    l4_msgtag_t tag;
    int ipc_stat = 0;
    l4_cap_idx_t th = l4re_util_cap_alloc();
    l4_exc_regs_t exc;
    l4_umword_t mr0, mr1;
    l4_utcb_t *u = l4_utcb();

    printf("Singlestep testing\n");

    if (l4_is_invalid_cap(th))
        return 1;

    l4_touch_rw(thread_stack, sizeof(thread_stack));
    l4_touch_ro(thread_func, 1);

    tag = l4_factory_create_thread(l4re_env()->factory, th);
    if (l4_error(tag))
        return 1;

    l4_thread_control_start();
    l4_thread_control_pager(l4re_env()->main_thread);
    l4_thread_control_exc_handler(l4re_env()->main_thread);
    l4_thread_control_bind((l4_utcb_t *)l4re_env()->first_free_utcb,
                          L4RE_THIS_TASK_CAP);
    l4_thread_control_alien(1);
    tag = l4_thread_control_commit(th);
    if (l4_error(tag))
        return 2;

    tag = l4_thread_ex_regs(th, (l4_umword_t)thread_func,
                          (l4_umword_t)thread_stack + sizeof(thread_stack),
                          0);

    if (l4_error(tag))
        return 3;

    l4_sched_param_t sp = l4_sched_param(1, 0);
    tag = l4_scheduler_run_thread(l4re_env()->scheduler, th, &sp);
    if (l4_error(tag))
        return 4;

    /* Pager/Exception loop */
    if (l4_msgtag_has_error(tag = l4_ipc_receive(th, u, L4_IPC_NEVER)))
    {
        printf("l4_ipc_receive failed");
        return 5;
    }
    memcpy(&exc, l4_utcb_exc(), sizeof(exc));
    mr0 = l4_utcb_mr()->mr[0];
    mr1 = l4_utcb_mr()->mr[1];

    for (;;)
    {
        if (l4_msgtag_is_exception(tag))
        {
            printf("PC = %08lx Trap = %08lx Err = %08lx, SP = %08lx SC-Nr: %lx\n",
                  l4_utcb_exc_pc(&exc), exc.trapno, exc.err,
                  exc.sp, exc.err >> 3);
            if (exc.err >> 3)
            {
                if (!(exc.err & 4))
                {
                    tag = l4_msgtag(L4_PROTO_ALLOW_SYSCALL,
                                    L4_UTCB_EXCEPTION_REGS_SIZE, 0, 0);
                    if (ipc_stat)
                        l4_kd_enter("Should not be 1");
                }
                else
                {
                    tag = l4_msgtag(L4_PROTO_NONE,
                                    L4_UTCB_EXCEPTION_REGS_SIZE, 0, 0);
                    if (!ipc_stat)
                        l4_kd_enter("Should not be 0");
                }
                ipc_stat = !ipc_stat;
            }
            l4_sleep(100);
        }
        else
            printf("Umm, non-handled request: %ld, %08lx %08lx\n",

```

```

        l4_msgtag_label(tag), mr0, mr1);

memcpy(l4_utcb_exc(), &exc, sizeof(exc));

/* Reply and wait */
if (l4_msgtag_has_error(tag = l4_ipc_call(th, u, tag, L4_IPC_NEVER)))
{
    printf("l4_ipc_call failed\n");
    return 5;
}
memcpy(&exc, l4_utcb_exc(), sizeof(exc));
mr0 = l4_utcb_mr()->mr[0];
mr1 = l4_utcb_mr()->mr[1];
}

return 0;
}

```

## 17.6 examples/sys/aliens/main.c

This example shows how system call tracing can be done.

This example shows how system call tracing can be done.

```

/* SPDX-License-Identifier: MIT */
/*
 * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
 *      Alexander Warg <warg@os.inf.tu-dresden.de>,
 *      Björn Döbel <doebel@os.inf.tu-dresden.de>
 */
/*
 * Example to show syscall tracing.
 */
#ifdef ARCH_x86 || defined(ARCH_amd64)
// MEASURE only works on x86/amd64
#define MEASURE
#endif

#include <l4/sys/ipc.h>
#include <l4/sys/thread.h>
#include <l4/sys/factory.h>
#include <l4/sys/scheduler.h>
#include <l4/sys/utcb.h>
#include <l4/util/util.h>
#include <l4/re/env.h>
#include <l4/re/c/util/cap_alloc.h>
#include <l4/re/c/util/kumem_alloc.h>
#include <l4/sys/debugger.h>

#include <stdlib.h>
#include <stdio.h>
#include <string.h>

/* Architecture specifics */
#ifdef ARCH_x86 || defined(ARCH_amd64)

static int
is_alien_after_call(l4_exc_regs_t const *exc)
{
    if defined(ARCH_x86)
        return exc->err & 4;
    else
        return exc->err == 1;
    #endif
}

static inline void
_print_exc_state(l4_exc_regs_t const *exc)
{
    printf("PC=%08lx SP=%08lx Err=%08lx Trap=%lx, %s syscall, SC-Nr: %lx\n",
        l4_utcb_exc_pc(exc), exc->sp, exc->err,
        exc->trapno, is_alien_after_call(exc) ? "after" : "before",
        exc->err >> 3);
}

#elif defined(ARCH_arm)

static int
is_alien_after_call(l4_exc_regs_t const *exc)
{
    return exc->err & 0x40; } // TODO: Should change this to (1 < 16)

static inline void

```

```

_print_exc_state(l4_exc_regs_t const *exc)
{
    printf("PC=%08lx SP=%08lx ULR=%08lx CPSR=%08lx Err=%lx/%lx, %s syscall\n",
        l4_utcb_exc_pc(exc), exc->sp, exc->ulr, exc->cpsr,
        exc->err, exc->err » 26,
        is_alien_after_call(exc) ? " after" : "before");
}

#elif defined(ARCH_arm64)

static int
is_alien_after_call(l4_exc_regs_t const *exc)
{ return exc->err & (1ul « 16); }

static inline void
_print_exc_state(l4_exc_regs_t const *exc)
{
    printf("PC=%08lx SP=%08lx PSTATE=%08lx Err=%lx/%lx, %s syscall\n",
        l4_utcb_exc_pc(exc), exc->sp, exc->pstate,
        exc->err, exc->err » 26,
        is_alien_after_call(exc) ? " after" : "before");
}

#elif defined(ARCH_mips)

static int
is_alien_after_call(l4_exc_regs_t const *exc)
{ return 0; }

static inline void
_print_exc_state(l4_exc_regs_t const *exc)
{
    printf("PC=%08lx SP=%08lx Cause=%lx, %s syscall\n",
        l4_utcb_exc_pc(exc), exc->sp, exc->cause,
        is_alien_after_call(exc) ? " after" : "before");
}

#elif defined(ARCH_riscv)

static int
is_alien_after_call(l4_exc_regs_t const *exc)
{ return exc->cause == L4_riscv_ec_l4_alien_after_syscall; }

static inline void
_print_exc_state(l4_exc_regs_t const *exc)
{
    printf("PC=%08lx SP=%08lx Cause=%lx, %s syscall\n",
        l4_utcb_exc_pc(exc), exc->sp, exc->cause,
        is_alien_after_call(exc) ? " after" : "before");
}

#else

static int
is_alien_after_call(l4_exc_regs_t const *exc)
{ return exc->err & 1; }

static inline void
_print_exc_state(l4_exc_regs_t const *exc)
{
    printf("PC=%08lx SP=%08lx, %s syscall\n",
        l4_utcb_exc_pc(exc), exc->sp,
        is_alien_after_call(exc) ? " after" : "before");
}

#endif

/* Measurement mode specifics.
 *
 * In measurement mode the code is less verbose and uses RDTSC for alien exception
 * performance measurement.
 */
#ifdef MEASURE

#include <l4/util/rdtsc.h>

static inline void
calibrate_timer(void)
{
    l4_calibrate_tsc(l4re_kip());
}

static inline void
print_timediff(l4_cpu_time_t start)
{
    e = l4_rdtsc();
    printf("time %lld\n", l4_tsc_to_ns(e - start));
}

```

```

}

static inline void
alien_sleep(void)
{
    l4_sleep(0);
}

static inline void
print_exc_state(l4_exc_regs_t const *exc)
{
    if (0)
        _print_exc_state(exc);
}

#else

static inline void
calibrate_timer(void)
{
}

static inline void
print_timediff(l4_cpu_time_t start)
{
    (void)start;
}

static inline l4_cpu_time_t
l4_rdtsc(void)
{
    return 0;
}

static inline void
alien_sleep(void)
{
    l4_sleep(1000);
}

static inline void
print_exc_state(l4_exc_regs_t const *exc)
{
    _print_exc_state(exc);
}

#endif

static char alien_thread_stack[8 « 10];
static l4_cap_idx_t alien;

static void alien_thread(void)
{
    while (1)
    {
        l4_ipc_call(0x1234 « L4_CAP_SHIFT, l4_utcb(),
                    l4_msgtag(0, 0, 0, 0), L4_IPC_NEVER);
        alien_sleep();
    }
}

int main(void)
{
    l4_msgtag_t tag;
    l4_cpu_time_t s;
    l4_utcb_t *u = l4_utcb();
    l4_exc_regs_t exc;
    l4_umword_t mr0, mr1;

    printf("Alien feature testing\n");

    l4_debugger_set_object_name(l4re_env()->main_thread, "alientest");

    /* Start alien thread */
    if (l4_is_invalid_cap(alien = l4re_util_cap_alloc()))
        return 1;

    l4_touch_rw(alien_thread_stack, sizeof(alien_thread_stack));

    tag = l4_factory_create_thread(l4re_env()->factory, alien);
    if (l4_error(tag))
        return 2;

    l4_debugger_set_object_name(alien, "alienth");

    l4_addr_t kumem;

```

```

if (l4re_util_kumem_alloc(&kumem, 0, L4RE_THIS_TASK_CAP, l4re_env()->rm))
    return 3;

l4_thread_control_start();
l4_thread_control_pager(l4re_env()->main_thread);
l4_thread_control_exc_handler(l4re_env()->main_thread);
l4_thread_control_bind((l4_utcb_t *)kumem, L4RE_THIS_TASK_CAP);
l4_thread_control_alien(1);
tag = l4_thread_control_commit(alien);
if (l4_error(tag))
    return 4;

tag = l4_thread_ex_regs(alien,
                        (l4_umword_t)alien_thread,
                        (l4_umword_t)alien_thread_stack + sizeof(alien_thread_stack),
                        0);

if (l4_error(tag))
    return 5;

l4_sched_param_t sp = l4_sched_param(1, 0);
tag = l4_scheduler_run_thread(l4re_env()->scheduler, alien, &sp);
if (l4_error(tag))
    return 6;

calibrate_timer();

/* Pager/Exception loop */
if (l4_msgtag_has_error(tag = l4_ipc_receive(alien, u, L4_IPC_NEVER)))
{
    printf("l4_ipc_receive failed");
    return 7;
}

memcpy(&exc, l4_utcb_exc(), sizeof(exc));
mr0 = l4_utcb_mr()->mr[0];
mr1 = l4_utcb_mr()->mr[1];

for (;;)
{
    s = l4_rdtsc();

    if (l4_msgtag_is_exception(tag))
    {
        print_exc_state(&exc);
        tag = l4_msgtag(is_alien_after_call(&exc)
                        ? 0 : L4_PROTO_ALLOW_SYSCALL,
                        L4_UTCB_EXCEPTION_REGS_SIZE, 0, 0);
    }
    else
        printf("Umm, non-handled request (like PF): %lx %lx\n", mr0, mr1);

    memcpy(l4_utcb_exc(), &exc, sizeof(exc));

    /* Reply and wait */
    if (l4_msgtag_has_error(tag = l4_ipc_call(alien, u, tag, L4_IPC_NEVER)))
    {
        printf("l4_ipc_call failed\n");
        return 8;
    }

    memcpy(&exc, l4_utcb_exc(), sizeof(exc));
    mr0 = l4_utcb_mr()->mr[0];
    mr1 = l4_utcb_mr()->mr[1];
    print_timediff(s);
}

return 0;
}

```

## 17.7 examples/sys/utcb-ipc/main.c

This example shows how to send IPC using the UTCB to store payload.

This example shows how to send IPC using the UTCB to store payload.

```

/* SPDX-License-Identifier: MIT */
/*
 * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
 * Alexander Warg <warg@os.inf.tu-dresden.de>,
 * Björn Döbel <doebel@os.inf.tu-dresden.de>
 */
#include <l4/sys/ipc.h>

```



```

#include <l4/sys/thread.h>
#include <l4/sys/factory.h>
#include <l4/sys/utcb.h>
#include <l4/sys/task.h>
#include <l4/sys/vcon.h>
#include <l4/re/env.h>
#include <l4/re/c/util/cap_alloc.h>
#include <l4/re/c/util/kumem_alloc.h>
#include <l4/util/thread.h>

#include <stdio.h>
#include <string.h>

static unsigned char stack2[8 « 10] __attribute__((aligned(8)));
static l4_cap_idx_t thread1_cap, thread2_cap;

static void vlogprintn(const char *s, int l)
{
    if (l > L4_VCON_WRITE_SIZE)
        l = L4_VCON_WRITE_SIZE;

    l4_vcon_send(L4_BASE_LOG_CAP, s, l);
}

static void vlogprint(const char *s)
{
    vlogprintn(s, strlen(s));
}

static void vlogputc(const char c)
{
    vlogprintn(&c, 1);
}

static void thread1(void)
{
    l4_msgregs_t *mr = l4_utcb_mr();
    l4_msgtag_t tag;
    int i, j;

    printf("Thread1 up (%p)\n", l4_utcb());

    for (i = 0; i < 10; i++)
    {
        for (j = 0; j < L4_UTCB_GENERIC_DATA_SIZE; j++)
            mr->mr[j] = 'A' + (i + j) % ('~' - 'A' + 1);
        tag = l4_msgtag(0, L4_UTCB_GENERIC_DATA_SIZE, 0, 0);
        if (l4_msgtag_has_error(l4_ipc_send(thread2_cap, l4_utcb(), tag, L4_IPC_NEVER)))
            printf("IPC-send error\n");
    }

    mr->mr[0] = 1;
    if (l4_msgtag_has_error(l4_ipc_send(thread2_cap, l4_utcb(), tag, L4_IPC_NEVER)))
        printf("IPC-send error\n");

    printf("Thread1 done\n");
}

L4UTIL_THREAD_STATIC_FUNC(thread2)
{
    l4_msgtag_t tag;
    l4_msgregs_t mr;
    unsigned i;

    // No printf() here because this would require a working pthread environment!
    vlogprint("Thread2 up\n");

    while (1)
    {
        if (l4_msgtag_has_error(tag = l4_ipc_receive(thread1_cap, l4_utcb(), L4_IPC_NEVER)))
            vlogprint("IPC receive error\n");
        memcpy(&mr, l4_utcb_mr(), sizeof(mr));
        if (mr.mr[0] == 1) // exit notification
            break;
        vlogprint("Thread2 receive: ");
        for (i = 0; i < l4_msgtag_words(tag); i++)
            vlogputc((char)mr.mr[i]);
        vlogprint("\n");
    }

    vlogprint("Thread2 done, switching to thread1\n");
    if (l4_msgtag_has_error(l4_ipc_send(thread1_cap, l4_utcb(),
                                      tag, L4_IPC_NEVER)))
        vlogprint("IPC-send error\n");

    // In theory this could hit if the above IPC send operation doesn't switch
    // to the other thread.

```

```

    __builtin_trap();
}

int main(void)
{
    l4_msgtag_t tag;

    thread1_cap = l4re_env()->main_thread;
    thread2_cap = l4re_util_cap_alloc();

    if (l4_is_invalid_cap(thread2_cap))
    {
        printf("Cannot allocate thread2 capability\n");
        return 1;
    }

    tag = l4_factory_create_thread(l4re_env()->factory, thread2_cap);
    if (l4_error(tag))
    {
        printf("Cannot create thread2\n");
        return 2;
    }

    l4_addr_t kumem;
    if (l4re_util_kumem_alloc(&kumem, 0, L4RE_THIS_TASK_CAP, l4re_env()->rm)
    {
        printf("Cannot allocate UTCB for thread2\n");
        return 3;
    }

    l4_thread_control_start();
    l4_thread_control_pager(l4re_env()->rm);
    l4_thread_control_exc_handler(l4re_env()->rm);
    l4_thread_control_bind((l4_utcb_t *)kumem, L4RE_THIS_TASK_CAP);
    tag = l4_thread_control_commit(thread2_cap);
    if (l4_error(tag))
    {
        printf("Cannot set thread2 thread parameters\n");
        return 4;
    }

    tag = l4_thread_ex_regs(thread2_cap,
                           (l4_umword_t)thread2,
                           (l4_umword_t)(stack2 + sizeof(stack2)), 0);
    if (l4_error(tag))
    {
        printf("Cannot set thread2 IP/SP\n");
        return 5;
    }

    l4_sched_param_t sp = l4_sched_param(1, 0);
    tag = l4_scheduler_run_thread(l4re_env()->scheduler, thread2_cap, &sp);
    if (l4_error(tag))
    {
        printf("Cannot start thread2\n");
        return 6;
    }

    thread1();

    if (l4_msgtag_has_error(l4_ipc_receive(thread2_cap, l4_utcb(),
                                           L4_IPC_NEVER)))
        printf("IPC-receive error\n");

    l4_task_unmap(L4RE_THIS_TASK_CAP,
                 l4_obj_fpage(thread2_cap, 0, L4_FPAGE_RWX),
                 L4_FP_ALL_SPACES);

    printf("Terminated thread2. Terminating.\n");
    return 0;
}

```

## 17.8 examples/sys/isr/main.c

Example of an interrupt service routine.

Example of an interrupt service routine.

```

/* SPDX-License-Identifier: MIT */
/*
 * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,

```

```

*           Alexander Warg <warg@os.inf.tu-dresden.de>,
*           Björn Döbel <doebel@os.inf.tu-dresden.de>
*/
/*
* This example shall show how to connect to an interrupt, receive interrupt
* events and detach again. As the interrupt source we'll use the virtual
* key interrupt -- pin 0 of the log capability.
*/

#include <l4/re/c/util/cap_alloc.h>
#include <l4/re/c/namespace.h>
#include <l4/sys/factory.h>
#include <l4/sys/icu.h>
#include <l4/sys/irq.h>
#include <l4/sys/vcon.h>
#include <l4/sys/utcb.h>

#include <stdio.h>

int main(void)
{
    int const irqno = 0;
    l4_cap_idx_t irqcap, icucap;
    l4_vcon_attr_t attr;
    long err;

    icucap = l4re_env()->log;

    /* Get a free capability slot for the ICU capability. */
    if (l4_is_invalid_cap(icucap))
    {
        printf("Did not find the Vlog ICU.\n");
        return 1;
    }

    /* Get another free capability slot for the corresponding IRQ object. */
    if (l4_is_invalid_cap(irqcap = l4re_util_cap_alloc()))
    {
        printf("Cannot allocate capability slot.\n");
        return 1;
    }

    /* Create IRQ object. */
    if ((err = l4_error(l4_factory_create_irq(l4re_env()->factory, irqcap)))
    {
        printf("Could not create IRQ object: %ld (%s).\n", err, l4sys_errtostr(err));
        return 1;
    }

    /*
    * Bind the recently allocated IRQ object to the IRQ number irqno as provided
    * by the ICU.
    */
    if ((err = l4_error(l4_icu_bind(icucap, irqno, irqcap)))
    {
        printf("Could not bind IRQ%d to ICU: %ld (%s).\n", irqno, err, l4sys_errtostr(err));
        return 1;
    }

    if ((err = l4_error(l4_vcon_get_attr(icucap, &attr)))
    {
        printf("Could not get Vcon attributes: %ld (%s).\n", err, l4sys_errtostr(err));
        return 1;
    }

    /* Disable echo at Vcon console. */
    attr.l_flags &= ~L4_VCON_ECHO;

    if ((err = l4_error(l4_vcon_set_attr(icucap, &attr)))
    {
        printf("Could not set Vcon attributes: %ld (%s).\n", err, l4sys_errtostr(err));
        return 1;
    }

    printf("Vcon echo disabled.\n");

    /* Bind ourselves to the IRQ. Define the IPC label which is sent if an IRQ
    * IPC arrives. */
    if ((err = l4_error(l4_rcv_ep_bind_thread(irqcap, l4re_env()->main_thread, 0x1234)))
    {
        printf("Could not bind to IRQ%d: %ld (%s).\n", irqno, err, l4sys_errtostr(err));
        return 1;
    }

    printf("Attached to key IRQ %d.\nPress keys now, Shift-Q to exit.\n", irqno);

    /* IRQ receive loop. */

```

```

while (1)
{
    /* Wait for the interrupt to happen. If we received an IRQ, the label
     * return code is set to 0. If we didn't receive an IRQ, the error flag
     * in the message tag is set and l4_error() reads the IPC error code from
     * the UTCB. */
    l4_umword_t label;
    if ((err = l4_error(l4_irq_wait(irqcap, &label, L4_IPC_NEVER))))
        printf("Could not receive IRQ: %ld (%s).\n", err, l4sys_errtostr(err));
    else
    {
        char buf[128];
        int n;

        if (label != 0x1234)
        {
            printf("Unexpected label %0lx -- ignoring interrupt.\n", label);
            continue;
        }

        /* Process the interrupt -- may do a 'break' */
        printf("Got IRQ with expected label 0x%lX.\n", label);
        n = l4_vcon_read(icucap, buf, sizeof(buf));
        if (n < 0)
            printf("Could not read from Vcon interface: %d (%s).\n", n, l4sys_errtostr(n));
        else
        {
            unsigned i;
            int terminate = 0;
            for (i = 0; i < (unsigned)n && i < sizeof(buf); ++i)
            {
                int c = (unsigned char)buf[i];
                if (c >= 32 && c < 128) // Filter UTF-8 encodings.
                    printf("Got key '%c'.\n", c);
                else
                    printf("Got keycode %d.\n", c);
                if (buf[i] == 'Q')
                    terminate = 1;
            }

            if (terminate)
                break;
        }
    }

    /* We're done, detach from the interrupt. */
    if ((err = l4_error(l4_irq_detach(irqcap))))
        printf("Could not detach from IRQ: %ld (%s).\n", err, l4sys_errtostr(err));

    printf("Application terminated.\n");
    return 0;
}

```

## 17.9 examples/clntsrv/src/server.cc

Client/Server example using C++ infrastructure – Server implementation.

Client/Server example using C++ infrastructure – Server implementation.

```

/* SPDX-License-Identifier: MIT */
/*
 * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
 * Alexander Warg <warg@os.inf.tu-dresden.de>
 */
#include <stdio.h>
#include <l4/re/env>
#include <l4/re/util/cap_alloc>
#include <l4/re/util/object_registry>
#include <l4/re/util/br_manager>
#include <l4/sys/cxx/ipc_epiface>

#include "shared.h"

static L4Re::Util::Registry_server<> server;

class Calculation_server : public L4::Epiface_t<Calculation_server, Calc>
{
public:
    int op_sub(Calc::Rights, l4_uint32_t a, l4_uint32_t b, l4_uint32_t &res)
    {

```

```

    res = a - b;
    return 0;
}

int op_neg(Calc::Rights, l4_uint32_t a, l4_uint32_t &res)
{
    res = -a;
    return 0;
}
};

int
main()
{
    static Calculation_server calc;

    // Register calculation server
    if (!server.registry()->register_obj(&calc, "calc_server").is_valid())
    {
        printf("Could not register my service, is there a 'calc_server' in the caps table?\n");
        return 1;
    }

    printf("Welcome to the calculation server!\n"
           "I can do subtractions and negations.\n");

    // Wait for client requests
    server.loop();

    return 0;
}

```

## 17.10 examples/clntsrv/src/client.cc

Client/Server example using C++ infrastructure – Client implementation.

Client/Server example using C++ infrastructure – Client implementation.

```

/* SPDX-License-Identifier: MIT */
/*
 * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
 *             Alexander Warg <warg@os.inf.tu-dresden.de>
 */
#include <l4/sys/err.h>
#include <l4/sys/types.h>
#include <l4/re/env>
#include <l4/re/util/cap_alloc>

#include <stdio.h>
#include "shared.h"

int
main()
{
    L4::Cap<Calc> server = L4Re::Env::env()->get_cap<Calc>("calc_server");
    if (!server.is_valid())
    {
        printf("Could not get server capability!\n");
        return 1;
    }

    l4_uint32_t val1 = 8;
    l4_uint32_t val2 = 5;

    printf("Asking for %d - %d\n", val1, val2);
    if (server->sub(val1, val2, &val1))
    {
        printf("Error talking to server\n");
        return 1;
    }
    printf("Result of subtract call: %d\n", val1);

    printf("Asking for -%d\n", val1);
    if (server->neg(val1, &val1))
    {
        printf("Error talking to server\n");
        return 1;
    }
    printf("Result of negate call: %d\n", val1);

    return 0;
}

```

## 17.11 examples/clntsrv/src/shared.h

Client/Server example using C++ infrastructure – Shared header file.

Client/Server example using C++ infrastructure – Shared header file.

```
/* SPDX-License-Identifier: MIT */
/*
 * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>
 */

#pragma once

#include <l4/sys/capability>
#include <l4/sys/cxx/ipc_iface>

struct Calc : L4::Kobject_t<Calc, L4::Kobject, 0x44>
{
    L4_INLINE_RPC(int, sub, (l4_uint32_t a, l4_uint32_t b, l4_uint32_t *res));
    L4_INLINE_RPC(int, neg, (l4_uint32_t a, l4_uint32_t *res));
    typedef L4::Typeid::Rpc<sub_t, neg_t> Rpc;
};
```

## 17.12 examples/clntsrv/configs/clntsrv.cfg

Sample configuration file for the client/server example.

Sample configuration file for the client/server example.

```
-- vim:set ft=lua:

-- Include L4 functionality
local L4 = require("L4");

-- Some shortcut for less typing
local ld = L4.default_loader;

-- Channel for the two programs to talk to each other.
local calc_server = ld:new_channel();

-- The server program, getting the channel in server mode.
ld:start({ caps = { calc_server = calc_server:svr() },
         log = { "server", "blue" } },
        "rom/ex_clntsrv-server");

-- The client program, getting the 'calc_server' channel to be able to talk
-- to the server. The client will be started with a green log output.
ld:start({ caps = { calc_server = calc_server },
         log = { "client", "green" } },
        "rom/ex_clntsrv-client");
```

## 17.13 examples/libs/l4re/c/ma+rm.c

Coarse grained memory allocation, in C.

Coarse grained memory allocation, in C.

```
/* SPDX-License-Identifier: MIT */
/*
 * (c) 2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>
 */

#include <l4/re/c/mem_alloc.h>
#include <l4/re/c/rm.h>
#include <l4/re/c/util/cap_alloc.h>
#include <l4/sys/err.h>
#include <stdio.h>
#include <string.h>

static int allocate_mem(unsigned long size_in_bytes, unsigned long flags,
                        void **virt_addr)
{
    ...
}
```

```

int r;
l4re_ds_t ds;

/* Allocate a free capability index for our data space */
ds = l4re_util_cap_alloc();
if (l4_is_invalid_cap(ds))
    return -L4_ENOMEM;

size_in_bytes = l4_trunc_page(size_in_bytes);

/* Allocate memory via a dataspace */
if ((r = l4re_ma_alloc(size_in_bytes, ds, flags)))
    return r;

/* Make the dataspace visible in our address space */
*virt_addr = 0;
if ((r = l4re_rm_attach(virt_addr, size_in_bytes,
                        L4RE_RM_F_SEARCH_ADDR | L4RE_RM_F_RWX, ds, 0,
                        flags & L4RE_MA_SUPER_PAGES
                        ? L4_SUPERPAGESHIFT : L4_PAGESHIFT)))
{
    /* Free dataspace again */
    l4re_util_cap_free_um(ds);
    return r;
}

/* Done, virtual address is in virt_addr */
return 0;
}

static int free_mem(void *virt_addr)
{
    int r;
    l4re_ds_t ds;

    /* Detach memory from our address space */
    if ((r = l4re_rm_detach_ds(virt_addr, &ds)))
        return r;

    /* Free memory at our memory allocator */
    l4re_util_cap_free_um(ds);

    /* All went ok */
    return 0;
}

int main(void)
{
    void *virt;

    /* Allocate memory: 16k Bytes (usually) */
    if (allocate_mem(4 * L4_PAGESIZE, 0, &virt))
        return 1;

    printf("Allocated memory.\n");

    /* Do something with the memory */
    memset(virt, 0x12, 4 * L4_PAGESIZE);

    printf("Touched memory.\n");

    /* Free memory */
    if (free_mem(virt))
        return 2;

    printf("Freed and done. Bye.\n");

    return 0;
}

```

## 17.14 examples/libs/l4re/c++/mem\_alloc/ma+rm.cc

Coarse grained memory allocation, in C++.

Coarse grained memory allocation, in C++.

```

/* SPDX-License-Identifier: MIT */
/*
 * (c) 2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>
 */

#include <l4/re/mem_alloc>

```

```

#include <l4/re/rm>
#include <l4/re/env>
#include <l4/re/dataspace>
#include <l4/re/util/cap_alloc>
#include <l4/sys/err.h>
#include <cstdio>
#include <cstring>

static int allocate_mem(unsigned long size_in_bytes, unsigned long flags,
                        void **virt_addr)
{
    int r;
    L4::Cap<L4Re::Dataspace> d;

    /* Allocate a free capability index for our data space */
    d = L4Re::Util::cap_alloc.alloc<L4Re::Dataspace>();
    if (!d.is_valid())
        return -L4_ENOMEM;

    size_in_bytes = l4_trunc_page(size_in_bytes);

    /* Allocate memory via a dataspace */
    if ((r = L4Re::Env::env()->mem_alloc()->alloc(size_in_bytes, d, flags)))
        return r;

    /* Make the dataspace visible in our address space */
    *virt_addr = 0;
    if ((r = L4Re::Env::env()->rm()->attach(virt_addr, size_in_bytes,
                                           L4Re::Rm::F::Search_addr | L4Re::Rm::F::RW,
                                           L4::Ipc::make_cap_rw(d), 0,
                                           flags & L4Re::Mem_alloc::Super_pages
                                           ? L4_SUPERPAGESHIFT : L4_PAGESHIFT)))
        return r;

    /* Done, virtual address is in virt_addr */
    return 0;
}

static int free_mem(void *virt_addr)
{
    int r;
    L4::Cap<L4Re::Dataspace> ds;

    /* Detach memory from our address space */
    if ((r = L4Re::Env::env()->rm()->detach(virt_addr, &ds)))
        return r;

    /* Release and return capability slot to allocator */
    L4Re::Util::cap_alloc.free(ds, L4Re::Env::env()->task().cap());

    /* All went ok */
    return 0;
}

int main(void)
{
    void *virt;

    /* Allocate memory: 16k Bytes (usually) */
    if (allocate_mem(4 * L4_PAGESIZE, 0, &virt))
        return 1;

    printf("Allocated memory.\n");

    /* Do something with the memory */
    memset(virt, 0x12, 4 * L4_PAGESIZE);

    printf("Touched memory.\n");

    /* Free memory */
    if (free_mem(virt))
        return 2;

    printf("Freed and done. Bye.\n");

    return 0;
}

```

## 17.15 examples/libs/l4re/c++/shared\_ds/ds\_clnt.cc

Sharing memory between applications, client side.



Sharing memory between applications, client side.

```

/* SPDX-License-Identifier: MIT */
/*
 * (c) 2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
 *      Alexander Warg <warg@os.inf.tu-dresden.de>
 */

#include <l4/re/util/cap_alloc> // L4::Cap
#include <l4/re/dataspace>      // L4Re::Dataspace
#include <l4/re/rm>             // L4::Rm
#include <l4/re/env>            // L4::Env
#include <l4/sys/cache.h>

#include <cstring>
#include <cstdio>
#include <unistd.h>

#include "interface.h"

int main()
{
    /*
     * Try to get server interface cap.
     */

    L4::Cap<My_interface> svr = L4Re::Env::env()->get_cap<My_interface>("shm");
    if (!svr.is_valid())
    {
        printf("Could not get the server capability\n");
        return 1;
    }

    /*
     * Alloc data space cap slot
     */
    L4::Cap<L4Re::Dataspace> ds = L4Re::Util::cap_alloc.alloc<L4Re::Dataspace>();
    if (!ds.is_valid())
    {
        printf("Could not get capability slot!\n");
        return 1;
    }

    /*
     * Alloc server notifier IRQ cap slot
     */
    L4::Cap<L4::Irq> irq = L4Re::Util::cap_alloc.alloc<L4::Irq>();
    if (!irq.is_valid())
    {
        printf("Could not get capability slot!\n");
        return 1;
    }

    /*
     * Request shared data-space cap.
     */
    if (svr->get_shared_buffer(ds, irq))
    {
        printf("Could not get shared memory dataspace!\n");
        return 1;
    }

    /*
     * Attach to arbitrary region
     */
    char *addr = 0;
    int err = L4Re::Env::env()->rm()->attach(&addr, ds->size(),
                                           L4Re::Rm::F::Search_addr | L4Re::Rm::F::RW,
                                           L4::Ipc::make_cap_rw(ds));

    if (err < 0)
    {
        printf("Error attaching data space: %s\n", l4sys_errtostr(err));
        return 1;
    }

    printf("Content: %s\n", addr);

    // wait a bit for the demo effect
    printf("Sleeping a bit...\n");
    sleep(1);

    /*
     * Fill in new stuff
     */
    memset(addr, 0, ds->size());
    char const * const msg = "Hello from client, too!";
    printf("Setting new content in shared memory\n");
    snprintf(addr, strlen(msg)+1, msg);
}

```

```

l4_cache_clean_data((unsigned long)addr,
                    (unsigned long)addr + strlen(msg) + 1);

// notify the server
irq->trigger();

/*
 * Detach region containing addr, result should be Detached_ds (other results
 * only apply if we split regions etc.).
 */
err = L4Re::Env::env()->rm()->detach(addr, 0);
if (err)
    printf("Failed to detach region\n");

/* Free objects and capabilities, just for completeness. */
L4Re::Util::cap_alloc.free(ds, L4Re::This_task);
L4Re::Util::cap_alloc.free(irq, L4Re::This_task);

return 0;
}

```

## 17.16 examples/libs/l4re/c++/shared\_ds/ds\_srv.cc

Sharing memory between applications, server/creator side.

Sharing memory between applications, server/creator side.

```

/* SPDX-License-Identifier: MIT */
/*
 * (c) 2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
 * Alexander Warg <warg@os.inf.tu-dresden.de>
 */

#include <l4/re/env>
#include <l4/re/error_helper>
#include <l4/re/namespace>
#include <l4/re/util/cap_alloc>
#include <l4/re/util/object_registry>
#include <l4/re/dataspace>
#include <l4/cxx/ipc_server>
#include <l4/util/util.h>

#include <l4/sys/typeinfo_svr>

#include <cstring>
#include <cstdio>
#include <unistd.h>
#include <pthread.h>
#include <pthread-l4.h>
#include <thread>

#include "interface.h"

class My_server_obj : public L4::Server_object_t<L4::Kobject>
{
private:
    L4::Cap<L4Re::Dataspace> _shm;
    L4::Cap<L4::Irq> _irq;

public:
    explicit My_server_obj(L4::Cap<L4Re::Dataspace> shm, L4::Cap<L4::Irq> irq)
        : _shm(shm), _irq(irq)
    {}

    int dispatch(l4_umword_t obj, L4::Ipc::Iostream &ios);
};

int My_server_obj::dispatch(l4_umword_t obj, L4::Ipc::Iostream &ios)
{
    // we don't care about the original object reference, however
    // we could read out the access rights from the lowest 2 bits
    (void) obj;

    l4_msgtag_t t;
    ios » t; // extract the tag

    switch (t.label())
    {
    case L4::Meta::Protocol:
        // handle the meta protocol requests, implementing the

```

```

    // runtime dynamic type system for L4 objects.
    return L4::Util::handle_meta_request<My_interface>(ios);
case 0:
    // since we have just one operation we have no opcode dispatch,
    // and just return the data-space and the notifier IRQ capabilities
    ios << _shm << _irq;
    return 0;
default:
    // every other protocol is not supported.
    return -L4_EBADPROTO;
}
}

class Shm_observer : public L4::Irq_handler_object
{
private:
    char *_shm;

public:
    explicit Shm_observer(char *shm)
        : _shm(shm)
    {}

    int dispatch(l4_umword_t obj, L4::Ipc::Iostream &ios);
};

int Shm_observer::dispatch(l4_umword_t obj, L4::Ipc::Iostream &ios)
{
    // We don't care about the original object reference, however
    // we could read out the access rights from the lowest 2 bits
    (void)obj;

    // Since we end up here in this function, we got a 'message' from the IRQ
    // that is bound to us. The 'ios' stream won't contain any valuable info.
    (void)ios;

    printf("Client sent us: %s\n", _shm);

    return 0;
}

enum
{
    DS_SIZE = 4 << 12,
};

static char *get_ds(L4::Cap<L4Re::Dataspace> *_ds)
{
    *_ds = L4Re::Util::cap_alloc.alloc<L4Re::Dataspace>();
    if (!(*_ds).is_valid())
    {
        printf("Dataspace allocation failed.\n");
        return 0;
    }

    int err = L4Re::Env::env()->mem_alloc()->alloc(DS_SIZE, *_ds, 0);
    if (err < 0)
    {
        printf("mem_alloc->alloc() failed.\n");
        L4Re::Util::cap_alloc.free(*_ds);
        return 0;
    }

    /*
     * Attach DS to local address space
     */
    char *_addr = 0;
    err = L4Re::Env::env()->rm()->attach(&_addr, (*_ds)->size(),
                                         L4Re::Rm::F::Search_addr | L4Re::Rm::F::RW,
                                         L4::Ipc::make_cap_rw(*_ds));

    if (err < 0)
    {
        printf("Error attaching data space: %s\n", l4sys_errtostr(err));
        L4Re::Util::cap_alloc.free(*_ds);
        return 0;
    }

    /*
     * Success! Write something to DS.
     */
    printf("Attached DS\n");
    static char const * msg = "[DS] Hello from server!";
    snprintf(_addr, strlen(msg) + 1, msg);

    return _addr;
}

```

```

}

static void *server_thread(void *)
{
    L4::Cap<L4::Thread> l4_thread = Pthread::L4::cap(pthread_self());
    L4Re::Util::Registry_server<> server(l4_thread, L4Re::Env::env()->factory());

    L4::Cap<L4Re::Dataspace> ds;
    char *addr;

    if (!(addr = get_ds(&ds)))
        return nullptr;

    // First the IRQ handler, because we need it in the My_server_obj object
    Shm_observer observer(addr);

    // Registering the observer as an IRQ handler, this allocates an
    // IRQ object using the factory of our server.
    L4::Cap<L4::Irq> irq = server.registry()->register_irq_obj(&observer);

    // Now the initial server object shared with the client via our parent.
    // it provides the data-space and the IRQ capabilities to a client.
    My_server_obj server_obj(ds, irq);

    // Registering the server object to the capability 'shm' in our the L4Re::Env.
    // This capability must be provided by the parent. (see the shared_ds.lua)
    server.registry()->register_obj(&server_obj, "shm");

    // Run our server loop.
    server.loop();
}

int main()
{
    pthread_attr_t pattr;

    if (pthread_attr_init(&pattr))
        L4Re::throw_error(-L4_ENOMEM, "Initialize pthread attributes");

    pthread_t thr;
    L4Re::chksys(pthread_create(&thr, &pattr, server_thread, nullptr),
        "Create server thread");
    L4Re::chksys(pthread_attr_destroy(&pattr), "Destroy pthread attributes");

    l4_sleep_forever();

    return 0;
}

```

## 17.17 examples/libs/l4re/c++/shared\_ds/shared\_ds.cfg

Sharing memory between applications, configuration file.

Sharing memory between applications, configuration file.

```

-- Include L4 functionality
local L4 = require("L4");

-- Create a channel from the client to the server
local channel = L4.default_loader:new_channel();

-- Start the server, giving the channel with full server rights.
-- The server will have a yellow log output.
L4.default_loader:start(
{
    caps = { shm = channel:svr() },
    log = { "server", "yellow" }
},
"rom/ex_l4re_ds_srv"
);

-- Start the client, giving it the channel with read only rights. The
-- log output will be green.
L4.default_loader:start(
{
    caps = { shm = channel },
    log = { "client", "green" },
    l4re_dbg = L4.Dbg.Warn
},
"rom/ex_l4re_ds_clnt"
);

```

## 17.18 examples/libs/l4re/streammap/server.cc

Client/Server example showing how to map a page to another task – Server implementation.

Client/Server example showing how to map a page to another task – Server implementation. Note that there's also a shared memory library that supplies this functionality in more convenient way.

```

/* SPDX-License-Identifier: MIT */
/*
 * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
 *           Alexander Warg <warg@os.inf.tu-dresden.de>
 */
#include <stdio.h>
#include <l4/re/env>
#include <l4/re/util/cap_alloc>
#include <l4/re/util/object_registry>
#include <l4/cxx/ipc_server>

#include "shared.h"

static char page_to_map[L4_PAGESIZE] __attribute__((aligned(L4_PAGESIZE)));

static L4Re::Util::Registry_server<> server;

class Smap_server : public L4::Server_object_t<Mapper>
{
public:
    int dispatch(l4_umword_t obj, L4::Ipc::Iostream &ios);
};

int
Smap_server::dispatch(l4_umword_t, L4::Ipc::Iostream &ios)
{
    l4_msgtag_t t;
    ios » t;

    // We're only talking the Map_example protocol
    if (t.label() != Mapper::Protocol)
        return -L4_EBADPROTO;

    L4::Opcode opcode;
    ios » opcode;

    switch (opcode)
    {
    case Mapper::Do_map:
        l4_addr_t snd_base;
        ios » snd_base;
        // put something into the page to read it out at the other side
        snprintf(page_to_map, sizeof(page_to_map), "Hello from the server!");
        printf("Sending to client\n");
        // send page
        ios « L4::Ipc::Snd_fpage::mem((l4_addr_t)page_to_map, L4_PAGESHIFT,
                                     L4_FPAGE_RO, snd_base);

        return L4_EOK;
    default:
        return -L4_ENOSYS;
    }
}

int
main()
{
    static Smap_server smap;

    // Register server
    if (!server.registry()->register_obj(&smap, "smap").is_valid())
    {
        printf("Could not register my service, read-only namespace?\n");
        return 1;
    }

    printf("Welcome to the memory map example server!\n");

    // Wait for client requests
    server.loop();

    return 0;
}

```

## 17.19 examples/libs/l4re/streammap/client.cc

Client/Server example showing how to map a page to another task – Client implementation.

Client/Server example showing how to map a page to another task – Client implementation. Note that there's also a shared memory library that supplies this functionality in more convenient way.

```

/* SPDX-License-Identifier: MIT */
/*
 * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
 *               Alexander Warg <warg@os.inf.tu-dresden.de>
 */
#include <l4/sys/err.h>
#include <l4/sys/types.h>
#include <l4/re/env>
#include <l4/re/util/cap_alloc>
#include <l4/cxx/ipc_stream>

#include <stdio.h>

#include "shared.h"

static int
func_smap_call(L4::Cap<void> const &server)
{
    L4::Ipc::Iostream s(l4_utcb());
    l4_addr_t addr = 0;
    int err;

    if ((err = L4Re::Env::env()->rm()->reserve_area(&addr, L4_PAGESIZE,
                                                    L4Re::Rm::F::Search_addr)))
    {
        printf("The reservation of one page within our virtual memory failed with %d\n", err);
        return 1;
    }

    s << L4::Opcode(Mapper::Do_map)
      << (l4_addr_t)addr;
    s << L4::Ipc::Rcv_fpage::mem((l4_addr_t)addr, L4_PAGESHIFT, 0);
    int r = l4_error(s.call(server.cap(), Mapper::Protocol));
    if (r)
        return r; // failure

    printf("String sent by server: %s\n", (char *)addr);

    return 0; // ok
}

int
main()
{
    L4::Cap<void> server = L4Re::Env::env()->get_cap<void>("smap");
    if (!server.is_valid())
    {
        printf("Could not get capability slot!\n");
        return 1;
    }

    printf("Asking for page from server\n");

    if (func_smap_call(server))
    {
        printf("Error talking to server\n");
        return 1;
    }
    printf("It worked!\n");

    L4Re::Util::cap_alloc.free(server, L4Re::This_task);

    return 0;
}

```

## 17.20 examples/libs/l4re/streammap/streammap.cfg

Sample configuration file for the client/server map example.

Sample configuration file for the client/server map example.

```
-- vim:set ft=lua:

-- Include L4 functionality
local L4 = require("L4");

-- Channel for the communication between the server and the client.
local smap_channel = L4.default_loader:new_channel();

-- The server program, using the 'smap' channel in server
-- mode. The log prefix will be 'server', colored yellow.
L4.default_loader:start({ caps = { smap = smap_channel:svr() },
                        log = { "server", "yellow" } },
                        "rom/ex_smap-server");

-- The client program.
-- It is given the 'smap' channel to be able to talk to the server.
-- The log prefix will be 'client', colored green.
L4.default_loader:start({ caps = { smap = smap_channel },
                        log = { "client", "green" } },
                        "rom/ex_smap-client");
```

## 17.21 examples/libs/libirq/loop.c

libirq usage example using a self-created thread.

libirq usage example using a self-created thread.

```
/* SPDX-License-Identifier: MIT */
/*
 * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>
 */

#include <l4/irq/irq.h>
#include <l4/util/util.h>
#include <stdio.h>
#include <pthread.h>

enum { IRQ_NO = 17 };

static void isr_handler(void)
{
    printf("Got IRQ %d\n", IRQ_NO);
}

static void *isr_thread(void *data)
{
    l4irq_t *irq;
    (void) data;

    if (!(irq = l4irq_attach(IRQ_NO)))
        return NULL;

    while (1)
    {
        if (l4irq_wait(irq))
            continue;
        isr_handler();
    }

    return NULL;
}

int main(void)
{
    pthread_t thread;

    if (pthread_create(&thread, NULL, isr_thread, NULL))
        return 1;

    l4_sleep_forever();
    return 0;
}
```

## 17.22 examples/libs/libirq/async\_isr.c

libirq usage example using asynchronous ISR handler functionality.

libirq usage example using asynchronous ISR handler functionality.

```

/* SPDX-License-Identifier: MIT */
/*
 * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>
 */
/*
 * This example shall show how to use the libirq.
 */

#include <l4/irq/irq.h>
#include <l4/util/util.h>

#include <stdio.h>

enum { IRQ_NO = 17 };

static void isr_handler(void *data)
{
    (void) data;
    printf("Got IRQ %d\n", IRQ_NO);
}

int main(void)
{
    const int seconds = 5;
    l4irq_t *irqdesc;

    if (!(irqdesc = l4irq_request(IRQ_NO, isr_handler, 0, 0xff, 0)))
    {
        printf("Requesting IRQ %d failed\n", IRQ_NO);
        return 1;
    }

    printf("Attached to key IRQ %d\nPress keys now, will terminate in %d seconds\n",
           IRQ_NO, seconds);

    l4_sleep(seconds * 1000);

    if (l4irq_release(irqdesc))
    {
        printf("Failed to release IRQ\n");
        return 1;
    }

    printf("Bye\n");
    return 0;
}

```

## 17.23 examples/sys/migrate/thread\_migrate.cc

Thread migration example.

Thread migration example.

```

/* SPDX-License-Identifier: MIT */
/*
 * (c) 2008-2009 Author(s)
 */
#include <l4/sys/scheduler>
#include <l4/re/env>
#include <l4/re/util/cap_alloc>

#include <pthread-l4.h>
#include <unistd.h>
#include <stdio.h>
#include <string.h>

enum { NR_THREADS = 12 };
static L4::Cap<L4::Thread> threads[NR_THREADS];
static l4_umword_t cpu_map, cpu_nrs;

/* Function for the threads. The content is not really relevant, so lets
 * just sleep around a bit. */

```



```

static void *thread_fn(void *)
{
    while (1)
        sleep(1);

    return 0;
}

/* Check how many CPUs we have available.
 */
static int check_cpus(void)
{
    l4_sched_cpu_set_t cs = l4_sched_cpu_set(0, 0);

    if (l4_error(L4Re::Env::env()->scheduler()->info(&cpu_nrs, &cs)) < 0)
        return 1;

    cpu_map = cs.map;

    printf("%ld maximal supported CPUs.\n", cpu_nrs);
    if (cpu_nrs >= L4_MWORD_BITS)
    {
        printf("Will only handle %ld CPUs.\n", cpu_nrs);
        cpu_nrs = L4_MWORD_BITS;
    }
    else if (cpu_nrs == 1)
        printf("Only found 1 CPU.\n");

    return cpu_nrs < 2;
}

/* Create a couple of threads and store their capabilities in an array */
static int create_threads(void)
{
    unsigned i;

    for (i = 0; i < NR_THREADS; ++i)
    {
        pthread_t t;

        if (pthread_create(&t, NULL, thread_fn, NULL))
            return 1;

        threads[i] = L4::Cap<L4::Thread>(pthread_l4_cap(t));
    }
    printf("Created %d threads.\n", NR_THREADS);
    return 0;
}

/* Helper function to get the next CPU */
static unsigned get_next_cpu(unsigned c)
{
    unsigned x = c;
    for (;;)
    {
        x = (x + 1) % cpu_nrs;
        if (L4Re::Env::env()->scheduler()->is_online(x))
            return x;
        if (x == c)
            return c;
    }
}

/* Function that shuffles the threads on the available CPUs */
static void shuffle(void)
{
    unsigned start = 0;
    while (1)
    {
        unsigned t;
        unsigned c = start;
        for (t = 0; t < NR_THREADS; ++t)
        {
            l4_sched_param_t sp = l4_sched_param(20);
            c = get_next_cpu(c);
            sp.affinity = l4_sched_cpu_set(c, 0);
            if (l4_error(L4Re::Env::env()->scheduler()->run_thread(threads[t], sp)))
                printf("Error migrating thread%02d to CPU%02d\n", t, c);
            printf("Migrated Thread%02d -> CPU%02d\n", t, c);
        }

        start++;
        if (start == cpu_nrs)
            start = 0;
        sleep(1);
    }
}

```

```

}

int main(void)
{
    if (check_cpus())
        return 1;

    if (create_threads())
        return 1;

    shuffle();

    return 0;
}

```

## 17.24 examples/sys/migrate/thread\_migrate.cfg

Sample configuration file for the thread migration example.

Sample configuration file for the thread migration example.

```

-- vim:set ft=lua:

local L4 = require("L4");

-- The log prefix will be 'migrate', colored green.
L4.default_loader:start({ log = { "migrate", "green" } },
    "rom/ex_thread_migrate");

```

## 17.25 tmpfs/lib/src/fs.cc

Example file system for [L4Re::Vfs](#).

Example file system for [L4Re::Vfs](#).

```

/*
 * (c) 2010 Adam Lackorzynski <adam@os.inf.tu-dresden.de>,
 *      Alexander Warg <warg@os.inf.tu-dresden.de>
 *      economic rights: Technische Universität Dresden (Germany)
 * This file is part of TUD:OS and distributed under the terms of the
 * GNU Lesser General Public License 2.1.
 * Please see the COPYING-LGPL-2.1 file for details.
 */

#include <l4/l4re_vfs/backend>
#include <l4/cxx/string>
#include <l4/cxx/avl_tree>

#include <sys/stat.h>
#include <sys/ioctl.h>
#include <dirent.h>

#include <cstdio>
#include <cstdlib>
#include <cstring>

namespace {

using namespace L4Re::Vfs;
using cxx::Ref_ptr;

class File_data
{
public:
    File_data() : _buf(0), _size(0) {}

    unsigned long put(unsigned long offset,
        unsigned long bufsize, void *srcbuf);
    unsigned long get(unsigned long offset,
        unsigned long bufsize, void *dstbuf);

    unsigned long size(unsigned long offset);

```

```

    unsigned long size() const { return _size; }

    ~File_data() noexcept { free(_buf); }

private:
    void *_buf;
    unsigned long _size;
};

unsigned long
File_data::put(unsigned long offset, unsigned long bufsize, void *srcbuf)
{
    if (offset + bufsize > _size)
        size(offset + bufsize);

    if (!_buf)
        return 0;

    memcpy((char *)_buf + offset, srcbuf, bufsize);
    return bufsize;
}

unsigned long
File_data::get(unsigned long offset, unsigned long bufsize, void *dstbuf)
{
    unsigned long s = bufsize;

    if (offset > _size)
        return 0;

    if (offset + bufsize > _size)
        s = _size - offset;

    memcpy(dstbuf, (char *)_buf + offset, s);
    return s;
}

unsigned long
File_data::size(unsigned long offset)
{
    if (offset != _size)
    {
        _size = offset;
        _buf = realloc(_buf, _size);
    }

    if (!_buf)
        return 0;
    return -ENOSPC;
}

class Node : public cxx::Avl_tree_node
{
public:
    Node(const char *path, mode_t mode)
        : _ref_cnt(0), _path(strdup(path))
    {
        memset(&_info, 0, sizeof(_info));
        _info.st_mode = mode;
    }

    const char *path() const { return _path; }
    struct stat64 *info() { return &_info; }

    void add_ref() noexcept { ++_ref_cnt; }
    int remove_ref() noexcept { return --_ref_cnt; }

    bool is_dir() const { return S_ISDIR(_info.st_mode); }

    virtual ~Node() { free(_path); }

private:
    int _ref_cnt;
    char *_path;
    struct stat64 _info;
};

struct Node_get_key
{
    typedef cxx::String Key_type;
    static Key_type key_of(Node const *n)
    { return n->path(); }
};

struct Path_avl_tree_compare
{

```

```

bool operator () (const char *l, const char *r) const
{ return strcmp(l, r) < 0; }
bool operator () (const cxx::String l, const cxx::String r) const
{
    int v = strncmp(l.start(), r.start(), cxx::min(l.len(), r.len()));
    return v < 0 || (v == 0 && l.len() < r.len());
}
};

class Pers_file : public Node
{
public:
    Pers_file(const char *name, mode_t mode)
        : Node(name, (mode & 0777) | S_IFREG) {}
    File_data const &data() const { return _data; }
    File_data &data() { return _data; }
private:
    File_data _data;
};

class Pers_dir : public Node
{
private:
    typedef cxx::Avl_tree<Node, Node_get_key, Path_avl_tree_compare> Tree;
    Tree _tree;

public:
    Pers_dir(const char *name, mode_t mode)
        : Node(name, (mode & 0777) | S_IFDIR) {}
    Ref_ptr<Node> find_path(cxx::String);
    bool add_node(Ref_ptr<Node> const &);

    typedef Tree::Const_iterator Const_iterator;
    Const_iterator begin() const { return _tree.begin(); }
    Const_iterator end() const { return _tree.end(); }
};

Ref_ptr<Node> Pers_dir::find_path(cxx::String path)
{
    return cxx::ref_ptr(_tree.find_node(path));
}

bool Pers_dir::add_node(Ref_ptr<Node> const &n)
{
    bool e = _tree.insert(n.ptr()).second;
    if (e)
        n->add_ref();
    return e;
}

class Tmpfs_dir : public Be_file
{
public:
    explicit Tmpfs_dir(Ref_ptr<Pers_dir> const &d) noexcept
        : _dir(d), _getdents_state(false) {}
    int get_entry(const char *, int, mode_t, Ref_ptr<File> *) noexcept override;
    ssize_t getdents(char *, size_t) noexcept override;
    int fstat(struct stat64 *buf) const noexcept override;
    int utime(const struct utimbuf *) noexcept override;
    int fchmod(mode_t) noexcept override;
    int mkdir(const char *, mode_t) noexcept override;
    int unlink(const char *) noexcept override;
    int rename(const char *, const char *) noexcept override;
    int faccessat(const char *, int, int) noexcept override;

private:
    int walk_path(cxx::String const &s,
                 Ref_ptr<Node> *ret, cxx::String *remaining = 0);

    Ref_ptr<Pers_dir> _dir;
    bool _getdents_state;
    Pers_dir::Const_iterator _getdents_iter;
};

class Tmpfs_file : public Be_file_pos
{
public:
    explicit Tmpfs_file(Ref_ptr<Pers_file> const &f) noexcept
        : Be_file_pos(), _file(f) {}

    off64_t size() const noexcept;
    int fstat(struct stat64 *buf) const noexcept override;
    int ftruncate(off64_t p) noexcept override;
    int ioctl(unsigned long, va_list) noexcept override;
    int utime(const struct utimbuf *) noexcept override;

```

```

    int fchmod(mode_t) noexcept override;

private:
    ssize_t preadv(const struct iovec *v, int iovcnt, off64_t p) noexcept
        override;
    ssize_t pwritev(const struct iovec *v, int iovcnt, off64_t p) noexcept
        override;
    Ref_ptr<Pers_file> _file;
};

ssize_t Tmpfs_file::preadv(const struct iovec *v, int iovcnt, off64_t p)
    noexcept
{
    if (iovcnt < 0)
        return -EINVAL;

    ssize_t sum = 0;
    for (int i = 0; i < iovcnt; ++i)
    {
        sum += _file->data().get(p, v[i].iov_len, v[i].iov_base);
        p += v[i].iov_len;
    }
    return sum;
}

ssize_t Tmpfs_file::pwritev(const struct iovec *v, int iovcnt, off64_t p)
    noexcept
{
    if (iovcnt < 0)
        return -EINVAL;

    ssize_t sum = 0;
    for (int i = 0; i < iovcnt; ++i)
    {
        sum += _file->data().put(p, v[i].iov_len, v[i].iov_base);
        p += v[i].iov_len;
    }
    return sum;
}

int Tmpfs_file::fstat(struct stat64 *buf) const noexcept
{
    _file->info()->st_size = _file->data().size();
    memcpy(buf, _file->info(), sizeof(*buf));
    return 0;
}

int Tmpfs_file::ftruncate(off64_t p) noexcept
{
    if (p < 0)
        return -EINVAL;

    if (_file->data().size(p) == 0)
        return 0;

    return -EIO; // most likely ENOSPC, but can't report that
}

off64_t Tmpfs_file::size() const noexcept
{
    return _file->data().size();
}

int
Tmpfs_file::ioctl(unsigned long v, va_list args) noexcept
{
    switch (v)
    {
        {
            case FIONREAD: // return amount of data still available
                int *available = va_arg(args, int *);
                *available = _file->data().size() - pos();
                return 0;
            };
        }
    return -EINVAL;
}

int
Tmpfs_file::utime(const struct utimbuf *times) noexcept
{
    _file->info()->st_atime = times->actime;
    _file->info()->st_mtime = times->modtime;
    return 0;
}

int
Tmpfs_file::fchmod(mode_t m) noexcept
{
    _file->info()->st_mode = m;
    return 0;
}

```

```

}

int
Tmpfs_dir::faccessat(const char *path, int mode, int) noexcept
{
    Ref_ptr<Node> node;
    cxx::String name = path;

    int err = walk_path(name, &node, &name);
    if (err < 0)
        return err;

    if (mode == F_OK) // existence check
        return 0;

    struct stat64 *stats = node->info();

    if ((mode & R_OK) && !(stats->st_mode & S_IRUSR))
        return -EACCES;

    if ((mode & W_OK) && !(stats->st_mode & S_IWUSR))
        return -EACCES;

    if ((mode & X_OK) && !(stats->st_mode & S_IXUSR))
        return -EACCES;

    return 0;
}

int
Tmpfs_dir::get_entry(const char *name, int flags, mode_t mode,
                    Ref_ptr<File> *file) noexcept
{
    Ref_ptr<Node> path;
    if (!*name)
    {
        *file = cxx::ref_ptr(this);
        return 0;
    }

    cxx::String n = name;

    int e = walk_path(n, &path, &n);

    if (e == -ENOTDIR)
        return e;

    if (!(flags & O_CREAT) && e < 0)
        return e;

    if ((flags & O_CREAT) && e == -ENOENT)
    {
        Ref_ptr<Node> node(new Pers_file(n.start(), mode));
        // when ENOENT is return, path is always a directory
        bool e = cxx::ref_ptr_static_cast<Pers_dir>(path)->add_node(node);
        if (!e)
            return -ENOMEM;
        path = node;
    }

    if (path->is_dir())
        *file = cxx::ref_ptr(new Tmpfs_dir(cxx::ref_ptr_static_cast<Pers_dir>(path)));
    else
        *file = cxx::ref_ptr(new Tmpfs_file(cxx::ref_ptr_static_cast<Pers_file>(path)));

    if (!*file)
        return -ENOMEM;

    return 0;
}

ssize_t
Tmpfs_dir::getdents(char *buf, size_t sz) noexcept
{
    struct dirent64 *d = (struct dirent64 *)buf;
    ssize_t ret = 0;

    if (!_getdents_state)
    {
        _getdents_iter = _dir->begin();
        _getdents_state = true;
    }
    else if (_getdents_iter == _dir->end())
    {
        _getdents_state = false;
        return 0;
    }

```

```

    }

    for (; _getdents_iter != _dir->end(); ++_getdents_iter)
    {
        unsigned l = strlen(_getdents_iter->path()) + 1;
        if (l > sizeof(d->d_name))
            l = sizeof(d->d_name);

        unsigned n = offsetof (struct dirent64, d_name) + l;
        n = (n + sizeof(long) - 1) & ~(sizeof(long) - 1);

        if (n > sz)
            break;

        d->d_ino = 1;
        d->d_off = 0;
        memcpy(d->d_name, _getdents_iter->path(), l);
        d->d_reclen = n;
        d->d_type = DT_REG;
        ret += n;
        sz -= n;
        d = (struct dirent64 *) ((unsigned long)d + n);
    }

    return ret;
}

int
Tmpfs_dir::fstat(struct stat64 *buf) const noexcept
{
    memcpy(buf, _dir->info(), sizeof(*buf));
    return 0;
}

int
Tmpfs_dir::utime(const struct utimbuf *times) noexcept
{
    _dir->info()->st_atime = times->actime;
    _dir->info()->st_mtime = times->modtime;
    return 0;
}

int
Tmpfs_dir::fchmod(mode_t m) noexcept
{
    _dir->info()->st_mode = m;
    return 0;
}

int
Tmpfs_dir::walk_path(cxx::String const &_s,
                    Ref_ptr<Node> *ret, cxx::String *remaining)
{
    Ref_ptr<Pers_dir> p = _dir;
    cxx::String s = _s;
    Ref_ptr<Node> n;

    while (1)
    {
        if (s.len() == 0)
        {
            *ret = p;
            return 0;
        }

        cxx::String::Index sep = s.find("/");

        if (sep - s.start() == 1 && *s.start() == '.')
        {
            s = s.substr(s.start() + 2);
            continue;
        }

        n = p->find_path(s.head(sep - s.start()));

        if (!n)
        {
            *ret = p;
            if (remaining)
                *remaining = s.head(sep - s.start());
            return -ENOENT;
        }

        if (sep == s.end())
        {
            *ret = n;
        }
    }
}

```

```

        return 0;
    }

    if (!n->is_dir())
        return -ENOTDIR;

    s = s.substr(sep + 1);

    p = cxx::ref_ptr_static_cast<Pers_dir>(n);
}

*ret = n;

return 0;
}

int
Tmpfs_dir::mkdir(const char *name, mode_t mode) noexcept
{
    Ref_ptr<Node> node = _dir;
    cxx::String p = cxx::String(name);
    cxx::String path, last = p;
    cxx::String::Index s = p.rfind("/");

    // trim /'s at the end
    while (p.len() && s == p.end() - 1)
    {
        p.len(p.len() - 1);
        s = p.rfind("/");
    }

    //printf("MKDIR '%s' p=%p %p\n", name, p.start(), s);

    if (s != p.end())
    {
        path = p.head(s);
        last = p.substr(s + 1, p.end() - s);

        int e = walk_path(path, &node);
        if (e < 0)
            return e;
    }

    if (!node->is_dir())
        return -ENOTDIR;

    // due to path walking we can end up with an empty name
    if (p.len() == 0 || p == cxx::String("."))
        return 0;

    Ref_ptr<Pers_dir> dnode = cxx::ref_ptr_static_cast<Pers_dir>(node);

    Ref_ptr<Pers_dir> dir(new Pers_dir(last.start(), mode));
    return dnode->add_node(dir) ? 0 : -EEXIST;
}

int
Tmpfs_dir::unlink(const char *name) noexcept
{
    cxx::Ref_ptr<Node> n;

    int e = walk_path(name, &n);
    if (e < 0)
        return -ENOENT;

    printf("Unimplemented (if file exists): %s(%s)\n", __func__, name);
    return -ENOMEM;
}

int
Tmpfs_dir::rename(const char *old, const char *newn) noexcept
{
    printf("Unimplemented: %s(%s, %s)\n", __func__, old, newn);
    return -ENOMEM;
}

class Tmpfs_fs : public Be_file_system
{
public:
    Tmpfs_fs() : Be_file_system("tmpfs") {}
    int mount(char const *source, unsigned long mountflags,
              void const *data, cxx::Ref_ptr<File> *dir) noexcept override
    {
        (void)mountflags;
        (void)source;
    }

```



```

    (void) data;
    *dir = cxx::ref_ptr(new Tmpfs_dir(cxx::ref_ptr(new Pers_dir("root", 0777))));
    if (!*dir)
        return -ENOMEM;
    return 0;
}
};

static Tmpfs_fs _tmpfs L4RE_VFS_FILE_SYSTEM_ATTRIBUTE;
}

```

## 17.26 examples/libs/shmc/prodcons.c

Simple shared memory example.

Simple shared memory example.

```

/*
 * (c) 2008-2009 Adam Lackorzynski <adam@os.inf.tu-dresden.de>
 *      economic rights: Technische Universität Dresden (Germany)
 *
 * This file is part of TUD:OS and distributed under the terms of the
 * GNU General Public License 2.
 * Please see the COPYING-GPL-2 file for details.
 */

/*
 * This example uses shared memory between two threads, one producer, one
 * consumer.
 */

#include <l4/shmc/shmc.h>

#include <l4/util/util.h>

#include <stdio.h>
#include <string.h>
#include <pthread-l4.h>

#include <l4/sys/thread.h>
#include <l4/sys/debugger.h>
#include <l4/sys/kip.h>
#include <l4/re/env.h>

#define LOG(args...)      printf(NAME ": " args)
#define CHK(func)
do
{
    long r = (func);
    if (r)
    {
        printf(NAME ": Failure %ld (%s) at line %d.\n",
               r, l4sys_errtostr(r), __LINE__);
        return (void *)-1;
    }
} while (0)

static const char some_data[] = "Hi consumer!";

static inline l4_cap_idx_t self(void) { return pthread_l4_cap(pthread_self()); }

#define NAME "PRODUCER"
static void *thread_producer(void *d)
{
    (void) d;
    l4shmc_chunk_t p_one;
    l4shmc_signal_t s_one, s_done;
    l4shmc_area_t shmarea;
    l4_kernel_clock_t try_until;

    l4_debugger_set_object_name(self(), "producer");

    // attach this thread to the shm object
    CHK(l4shmc_attach("testshm", &shmarea));

    // add a chunk
    CHK(l4shmc_add_chunk(&shmarea, "one", 1024, &p_one));

    // add a signal

```

```

CHK(l4shmc_add_signal(&shmarea, "testshm_prod", &s_one));

CHK(l4shmc_attach_signal(&shmarea, "testshm_done", self(), &s_done));

// connect chunk and signal
CHK(l4shmc_connect_chunk_signal(&p_one, &s_one));

CHK(l4shmc_mark_client_initialized(&shmarea));

try_until = l4_kip_clock(l4re_kip()) + 10 * 1000000;

for (;;)
{
    l4_umword_t clients;
    l4shmc_get_initialized_clients(&shmarea, &clients);
    if (clients == 3UL)
        break;
    if (l4_kip_clock(l4re_kip()) >= try_until)
    {
        LOG("consumer not initialized within time\n");
        return (void *)-1;
    }
}

LOG("Ready.\n");

while (1)
{
    while (l4shmc_chunk_try_to_take(&p_one))
        printf("Uh, should not happen!\n"); //l4_thread_yield();

    memcpy(l4shmc_chunk_ptr(&p_one), some_data, sizeof(some_data));

    CHK(l4shmc_chunk_ready_sig(&p_one, sizeof(some_data)));

    LOG("Sent data.\n");

    CHK(l4shmc_wait_signal(&s_done));
}

l4_sleep_forever();
return NULL;
}

#undef NAME
#define NAME "CONSUMER"
static void *thread_consumer(void *d)
{
    (void)d;
    l4shmc_area_t shmarea;
    l4shmc_chunk_t p_one;
    l4shmc_signal_t s_one, s_done;
    l4_kernel_clock_t try_until;

    l4_debugger_set_object_name(self(), "consumer");

    // attach to shared memory area
    CHK(l4shmc_attach("testshm", &shmarea));

    // get chunk 'one'
    CHK(l4shmc_get_chunk(&shmarea, "one", &p_one));

    // add a signal
    CHK(l4shmc_add_signal(&shmarea, "testshm_done", &s_done));

    // attach signal to this thread
    CHK(l4shmc_attach_signal(&shmarea, "testshm_prod", self(), &s_one));

    // connect chunk and signal
    CHK(l4shmc_connect_chunk_signal(&p_one, &s_one));

    CHK(l4shmc_mark_client_initialized(&shmarea));

    try_until = l4_kip_clock(l4re_kip()) + 10 * 1000000;

    for (;;)
    {
        l4_umword_t clients;
        l4shmc_get_initialized_clients(&shmarea, &clients);
        if (clients == 3UL)
            break;
        if (l4_kip_clock(l4re_kip()) >= try_until)
        {
            LOG("producer not initialized within time\n");
            return (void *)-1;
        }
    }
}

```

```
    }

    LOG("Ready.\n");

    while (1)
    {
        CHK(l4shmc_wait_chunk(&p_one));

        LOG("Received from chunk one: '%s'.\n",
            (char *)l4shmc_chunk_ptr(&p_one));
        memset(l4shmc_chunk_ptr(&p_one), 0, l4shmc_chunk_size(&p_one));

        CHK(l4shmc_chunk_consumed(&p_one));

        CHK(l4shmc_trigger(&s_done));
    }

    return NULL;
}

int main(void)
{
    pthread_t one, two;
    long r;

    // create shared memory area
    if ((r = l4shmc_create("testshm")) < 0)
    {
        printf("Error %ld (%s) creating shared memory area\n",
            r, l4sys_errtostr(r));
        return 1;
    }

    // create two threads, one for producer, one for consumer
    pthread_create(&one, 0, thread_producer, 0);
    pthread_create(&two, 0, thread_consumer, 0);

    // now sleep, the two threads are doing the work
    l4_sleep_forever();

    return 0;
}
```



# Index

%L4 Inter-Process Communication (IPC), [7](#)

\_\_lface

L4::Kobject\_2t< Derived, Base1, Base2, PROTO, S\_DEMAND >, [1290](#)

L4::Kobject\_3t< Derived, Base1, Base2, Base3, PROTO, S\_DEMAND >, [1294](#)

\_\_lface\_list

L4::Kobject\_2t< Derived, Base1, Base2, PROTO, S\_DEMAND >, [1290](#)

L4::Kobject\_3t< Derived, Base1, Base2, Base3, PROTO, S\_DEMAND >, [1294](#)

\_\_L4UTIL\_THREAD\_FUNC

thread.h, [2537](#)

\_\_check\_protocols\_\_

L4::Kobject\_2t< Derived, Base1, Base2, PROTO, S\_DEMAND >, [1291](#)

L4::Kobject\_3t< Derived, Base1, Base2, Base3, PROTO, S\_DEMAND >, [1295](#)

\_\_l4\_kdebug\_3\_text

kdebug.h, [3181](#)

\_\_l4\_kdebug\_op

kdebug.h, [3182](#)

\_\_l4\_kdebug\_op\_1

kdebug.h, [3183](#)

\_\_l4\_kdebug\_text

kdebug.h, [3185](#)

\_\_vcpu-arch.h

L4\_vcpu\_e\_field\_ids, [2492](#), [2496](#)

L4\_VCPU\_E\_VTMR\_CFG, [2493](#), [2496](#)

L4\_VCPU\_STATE\_VERSION, [2490](#), [2492](#), [2496](#), [2499](#)

~Be\_file\_system

L4Re::Vfs::Be\_file\_system, [1847](#)

~H\_list\_item\_t

cxx::H\_list\_item\_t< ELEM\_TYPE >, [901](#)

~Lock\_guard

L4::Lock\_guard, [1308](#)

~S

L4::Factory::S, [1070](#)

~Unique\_region

L4Re::Rm::Unique\_region< T >, [1743](#)

Rm::Unique\_region< T >, [2339](#)

a

L4Re::Video::Pixel\_info, [1911](#)

access\_once

cxx, [726](#)

Access\_width

L4Re::Mmio\_space, [1693](#)

acquire

L4Re::Inhibitor, [1662](#)

add

L4::lpc\_svr::Timeout\_queue, [1245](#)

L4::Thread::Modify\_senders, [1426](#)

L4::Thread\_group, [1429](#)

L4vcpu::State, [2015](#)

L4virtio::Svr::Driver\_mem\_list\_t< DATA >, [2174](#)

Virtio\_vlan\_mangle, [2359](#)

add\_block

L4virtio::Driver::Block\_device, [2042](#)

add\_image\_info

L4::Debugger, [1028](#)

add\_irq\_status

L4virtio::Svr::Dev\_config, [2151](#)

add\_ku\_mem

L4::Task, [1395](#)

add\_monitor\_port

Virtio\_switch, [2355](#)

add\_port

Virtio\_switch, [2355](#)

add\_timeout

L4::lpc\_svr::Server\_iface, [1236](#)

L4::lpc\_svr::Timeout\_queue\_hooks< HOOKS, BR\_MAN >, [1251](#)

add\_trusted\_dataspaces

L4virtio::Svr::Device\_t< DATA >, [2169](#)

alien

L4::Thread::Attr, [1421](#)

align\_to

L4::lpc::Msg, [752](#), [753](#)

all

L4::Kip::Mem\_desc, [1278](#)

alloc

cxx::Base\_slab< Obj\_size, Slab\_size, Max\_free, Alloc >, [811](#)

cxx::Base\_slab\_static< Obj\_size, Slab\_size, Max\_free, Alloc >, [816](#)

cxx::List\_alloc, [910](#)

cxx::Slab< Type, Slab\_size, Max\_free, Alloc >, [940](#)

cxx::Slab\_static< Type, Slab\_size, Max\_free, Alloc >, [945](#)

L4Re::Cap\_alloc, [1592](#), [1593](#)

L4Re::Mem\_alloc, [1685](#)

L4Re::Util::Cap\_alloc, [1750](#)

L4Re::Util::Counting\_cap\_alloc< COUNTER-TYPE, Dbg >, [1784](#)

alloc\_buffer\_demand

L4::lpc\_svr::Br\_manager\_no\_buffers, [1215](#)

- L4::lpc\_svr::Server\_iface, 1236
  - L4Re::Util::Br\_manager, 1770
- alloc\_descriptor
  - L4virtio::Driver::Virtqueue, 2074
- alloc\_dynamic\_entry
  - L4Re::Util::Names::Name\_space, 1813
- alloc\_fd
  - L4Re::Vfs::Fs, 1862
- alloc\_max
  - cxx::List\_alloc, 910
- allocate
  - L4Re::Dataspace, 1605
  - L4Re::Util::Dataspace\_svr, 1789
- AMD64 Virtual Registers (UTCB), 272
- amd64/l4/sys/\_\_kip-arch.h, 2487
- amd64/l4/sys/\_\_vcpu-arch.h, 2488, 2490
- amd64/l4/sys/arch/cache.h, 3037
- amd64/l4/sys/arch/consts.h, 3053, 3054
- amd64/l4/sys/arch/ipc.h, 3160
- amd64/l4/sys/arch/kip.h, 3342
- amd64/l4/sys/arch/l4int.h, 3205, 3206
- amd64/l4/sys/arch/platform\_control.h, 3223
- amd64/l4/sys/arch/task.h, 3253
- amd64/l4/sys/arch/thread.h, 2524
- amd64/l4/sys/arch/utcb.h, 3274, 3275
- amd64/l4/sys/ktrace\_events.h, 2500
- amd64/l4/sys/linkage.h, 2512, 2513
- amd64/l4/sys/segment.h, 2447, 2452
- amd64/l4/sys/vm.h, 2518
- amd64/l4/util/arch/l4\_macros.h, 2521
- amd64/l4/util/arch/thread.h, 2524
- amd64/l4/util/bitops\_arch.h, 2538, 2539
- amd64/l4/util/cpu.h, 2546, 2547
- amd64/l4/util/irq.h, 2683, 2684
- amd64/l4/util/mbi\_argv.h, 2551, 2552
- amd64/l4/util/perform.h, 2456, 2457
- amd64/l4/util/port\_io.h, 2468, 2470
- amd64/l4/util/rdtsc.h, 2476, 2478
- amd64/l4/util/spin.h, 2485, 2486
- Application and Server Building Blocks, 28
- Arch
  - L4::Kip::Mem\_desc, 1276
- Arch\_acpi\_nvs
  - L4::Kip::Mem\_desc, 1276
- Arch\_acpi\_tables
  - L4::Kip::Mem\_desc, 1276
- Arch\_sub\_type\_common
  - L4::Kip::Mem\_desc, 1275
- ARM Virtual Registers (UTCB), 271
- arm/l4/sys/\_\_kip-arch.h, 2487
- arm/l4/sys/\_\_vcpu-arch.h, 2491, 2493
- arm/l4/sys/arch/cache.h, 3038, 3039
- arm/l4/sys/arch/consts.h, 3054, 3055
- arm/l4/sys/arch/ipc.h, 3161
- arm/l4/sys/arch/kip.h, 3343
- arm/l4/sys/arch/l4int.h, 3206
- arm/l4/sys/arch/platform\_control.h, 3223
- arm/l4/sys/arch/task.h, 3253
- arm/l4/sys/arch/thread.h, 2524, 2525
- arm/l4/sys/arch/utcb.h, 3276, 3278
- arm/l4/sys/atomic.h, 3304
- arm/l4/sys/ktrace\_events.h, 2503
- arm/l4/sys/linkage.h, 2513, 2514
- arm/l4/sys/mem\_op.h, 2515, 2516
- arm/l4/sys/syscall\_defs.h, 2517, 2518
- arm/l4/sys/vm.h, 2518, 2519
- arm/l4/util/arch/l4\_macros.h, 2521, 2522
- arm/l4/util/arch/thread.h, 2525
- arm/l4/util/bitops\_arch.h, 2542, 2543
- arm/l4/util/cpu.h, 2548
- arm/l4/util/irq.h, 2684, 2685
- arm/l4/util/mbi\_argv.h, 2552, 2553
- ARM64 Virtual Registers (UTCB), 271
- arm64/l4/sys/\_\_kip-arch.h, 2488
- arm64/l4/sys/\_\_vcpu-arch.h, 2494, 2496
- arm64/l4/sys/arch/cache.h, 3040, 3042
- arm64/l4/sys/arch/consts.h, 3055, 3056
- arm64/l4/sys/arch/ipc.h, 3161
- arm64/l4/sys/arch/kip.h, 3343
- arm64/l4/sys/arch/l4int.h, 3207
- arm64/l4/sys/arch/platform\_control.h, 3224
- arm64/l4/sys/arch/task.h, 3253
- arm64/l4/sys/arch/thread.h, 2525, 2526
- arm64/l4/sys/arch/utcb.h, 3279, 3280
- arm64/l4/sys/ktrace\_events.h, 2506
- arm64/l4/sys/linkage.h, 2514
- arm64/l4/sys/vm.h, 2520
- arm\_smccc.h
  - l4\_arm\_smccc\_call, 3034
- assert.h
  - l4\_assert, 3300
- assign\_dma\_domain
  - L4vbus::Vbus, 2008, 2009
- associate
  - L4Re::Dma\_space, 1626
- AT\_BASE
  - ELF binary format, 691
- AT\_EGID
  - ELF binary format, 692
- AT\_ENTRY
  - ELF binary format, 691
- AT\_EUID
  - ELF binary format, 692
- AT\_EXECFD
  - ELF binary format, 691
- AT\_FLAGS
  - ELF binary format, 691
- AT\_GID
  - ELF binary format, 692
- AT\_IGNORE
  - ELF binary format, 691
- AT\_L4\_AUX
  - ELF binary format, 692
- AT\_L4\_ENV
  - ELF binary format, 692
- AT\_L4\_KIP

- ELF binary format, [692](#)
- AT\_NOTELF
  - ELF binary format, [691](#)
- AT\_NULL
  - ELF binary format, [691](#)
- AT\_PAGESZ
  - ELF binary format, [691](#)
- AT\_PHDR
  - ELF binary format, [691](#)
- AT\_PHENT
  - ELF binary format, [691](#)
- AT\_PHNUM
  - ELF binary format, [691](#)
- AT\_UID
  - ELF binary format, [691](#)
- Atomic Instructions, [658](#)
  - l4util\_add16, [660](#)
  - l4util\_add16\_res, [660](#)
  - l4util\_add32, [660](#)
  - l4util\_add32\_res, [661](#)
  - l4util\_add8, [661](#)
  - l4util\_add8\_res, [661](#)
  - l4util\_and16, [662](#)
  - l4util\_and16\_res, [662](#)
  - l4util\_and32, [662](#)
  - l4util\_and32\_res, [663](#)
  - l4util\_and8, [663](#)
  - l4util\_and8\_res, [663](#)
  - l4util\_atomic\_add, [664](#)
  - l4util\_atomic\_inc, [664](#)
  - l4util\_cmpxchg, [664](#)
  - l4util\_cmpxchg16, [665](#)
  - l4util\_cmpxchg32, [666](#)
  - l4util\_cmpxchg8, [666](#)
  - l4util\_dec16, [667](#)
  - l4util\_dec16\_res, [667](#)
  - l4util\_dec32, [667](#)
  - l4util\_dec32\_res, [668](#)
  - l4util\_dec8, [668](#)
  - l4util\_dec8\_res, [668](#)
  - l4util\_inc16, [668](#)
  - l4util\_inc16\_res, [669](#)
  - l4util\_inc32, [669](#)
  - l4util\_inc32\_res, [669](#)
  - l4util\_inc8, [670](#)
  - l4util\_inc8\_res, [670](#)
  - l4util\_or16, [670](#)
  - l4util\_or16\_res, [671](#)
  - l4util\_or32, [671](#)
  - l4util\_or32\_res, [671](#)
  - l4util\_or8, [671](#)
  - l4util\_or8\_res, [672](#)
  - l4util\_sub16, [672](#)
  - l4util\_sub16\_res, [672](#)
  - l4util\_sub32, [673](#)
  - l4util\_sub32\_res, [673](#)
  - l4util\_sub8, [673](#)
  - l4util\_sub8\_res, [674](#)
  - l4util\_xchg, [674](#)
  - l4util\_xchg16, [674](#)
  - l4util\_xchg32, [675](#)
  - l4util\_xchg8, [675](#)
- atomic\_clear\_bit
  - cxx::Bitmap\_base, [837](#)
  - L4Re::Util::Bitmap\_base, [1759](#)
- atomic\_get\_and\_clear
  - cxx::Bitmap\_base, [837](#)
  - L4Re::Util::Bitmap\_base, [1759](#)
- atomic\_get\_and\_set
  - cxx::Bitmap\_base, [838](#)
  - L4Re::Util::Bitmap\_base, [1759](#)
- atomic\_set\_bit
  - cxx::Bitmap\_base, [838](#)
  - L4Re::Util::Bitmap\_base, [1760](#)
- attach
  - L4Re::Rm, [1722](#), [1724](#)
  - L4Re::Util::Event\_buffer\_t< PAYLOAD >, [1801](#)
  - Rm, [2323](#), [2324](#)
- Attach\_flags
  - L4Re::Rm::F, [1738](#)
  - Rm::F, [2334](#)
- Attach\_mask
  - L4Re::Rm::F, [1738](#)
  - Rm::F, [2334](#)
- Attr
  - L4::Thread::Attr, [1421](#)
- Attribute
  - L4Re::Dma\_space, [1624](#)
- Attributes
  - L4Re::Dma\_space, [1624](#)
- Attributes and additional permissions for object send items, [231](#)
  - L4\_FPAGE\_C\_IPCGATE\_SVR, [232](#)
- atype
  - Elf32\_Auxv, [965](#)
  - Elf64\_Auxv, [975](#)
- Auxiliary data, [585](#)
- avail
  - cxx::List\_alloc, [911](#)
- avail\_align
  - L4virtio::Virtqueue, [2273](#)
- avail\_size
  - L4virtio::Virtqueue, [2273](#)
- Avl\_map
  - cxx::Avl\_map< KEY\_TYPE, DATA\_TYPE, COMPARE, ALLOC >, [792](#)
- Avl\_set\_iter
  - cxx::Bits::Avl\_set\_iter< Node, Key, Node\_op >, [852](#)
- ax
  - l4\_vcpu\_regs\_t, [1555](#)
- b
  - L4Re::Video::Pixel\_info, [1911](#), [1912](#)
- backtrace.h
  - l4util\_backtrace, [3314](#)
- Bad\_address

- L4virtio::Svr::Bad\_descriptor, [2083](#)
- Bad\_descriptor
  - L4virtio::Svr::Bad\_descriptor, [2083](#)
- Bad\_flags
  - L4virtio::Svr::Bad\_descriptor, [2083](#)
- Bad\_next
  - L4virtio::Svr::Bad\_descriptor, [2083](#)
- Bad\_rights
  - L4virtio::Svr::Bad\_descriptor, [2083](#)
- Bad\_size
  - L4virtio::Svr::Bad\_descriptor, [2083](#)
- Base API, [149](#)
- Base\_avl\_set
  - cxx::Bits::Base\_avl\_set< ITEM\_TYPE, COM-PARE, ALLOC, GET\_KEY >, [857](#)
- Basic Macros, [152](#)
  - I4\_align\_stack\_for\_direct\_fncall, [156](#)
  - L4\_EXPORT, [154](#)
  - L4\_HIDDEN, [154](#)
  - I4\_infinite\_loop, [157](#)
  - L4\_NOTHROW, [155](#)
- Be\_file\_system
  - L4Re::Vfs::Be\_file\_system, [1847](#)
- begin
  - cxx::Bits::Base\_avl\_set< ITEM\_TYPE, COM-PARE, ALLOC, GET\_KEY >, [858](#)
  - cxx::Bits::Bst< Node, Get\_key, Compare >, [872](#), [873](#)
- Bidirectional
  - L4Re::Dma\_space, [1625](#)
- bind
  - L4::lcu, [1079](#)
  - L4::lommu, [1096](#)
  - L4::Thread::Attr, [1421](#)
- bind\_notification\_irq
  - L4virtio::Driver::Device, [2050](#)
- bind\_rx\_notification\_irq
  - L4virtio::Driver::Virtio\_net\_device, [2064](#)
- bind\_snd\_destination
  - L4::Rcv\_endpoint, [1341](#)
- bind\_thread
  - L4::Rcv\_endpoint, [1341](#)
- bind\_vcpu
  - L4::Irq, [1258](#)
- bit
  - cxx::Bitmap\_base, [839](#), [840](#)
  - L4Re::Util::Bitmap\_base, [1760](#)
- Bit Manipulation, [676](#)
  - I4util\_bsf, [677](#)
  - I4util\_bsr, [678](#)
  - I4util\_btc, [678](#)
  - I4util\_btr, [678](#)
  - I4util\_bts, [679](#)
  - I4util\_clear\_bit, [680](#)
  - I4util\_complement\_bit, [680](#)
  - I4util\_find\_first\_set\_bit, [681](#)
  - I4util\_find\_first\_zero\_bit, [681](#)
  - I4util\_next\_power2, [681](#)
  - I4util\_set\_bit, [682](#)
  - I4util\_test\_bit, [682](#)
- bit\_index
  - cxx::Bitmap\_base, [841](#)
  - L4Re::Util::Bitmap\_base, [1761](#)
- Bits
  - cxx::Bitfield< T, LSB, MSB >, [821](#)
- bits\_per\_pixel
  - L4Re::Video::Pixel\_info, [1912](#)
- Bits\_type
  - cxx::Bitfield< T, LSB, MSB >, [820](#)
- Block\_dev\_base
  - L4virtio::Svr::Block\_dev\_base< Ds\_data >, [2088](#)
- Bootloader
  - L4::Kip::Mem\_desc, [1276](#)
- Bootstrap, the %L4 kernel bootstrapper, [91](#)
- bp
  - I4\_vcpu\_regs\_t, [1555](#)
- Br\_bytes
  - L4::lpc::Msg, [752](#)
- buf
  - L4Re::Util::Event\_buffer\_t< PAYLOAD >, [1801](#)
- buf\_cp\_in
  - L4::lpc, [744](#)
- buf\_cp\_out
  - L4::lpc, [745](#)
- buf\_in
  - L4::lpc, [745](#)
- Buffer, [785](#)
- buffer
  - L4Re::Util::Event\_t< PAYLOAD >, [1806](#)
- Buffer Registers (BRs), [269](#)
  - L4\_BDR\_IO\_SHIFT, [270](#)
  - L4\_BDR\_MEM\_SHIFT, [270](#)
  - L4\_BDR\_OBJ\_SHIFT, [270](#)
  - I4\_buffer\_desc\_consts\_t, [270](#)
- Bufferable
  - L4Re::Dataspace::F, [1616](#)
- Buffered
  - L4::lpc::Snd\_fpage, [1186](#)
- bus\_cap
  - L4vbus::Device, [1959](#)
- bx
  - I4\_vcpu\_regs\_t, [1555](#)
- bytes\_per\_pixel
  - L4Re::Video::Pixel\_info, [1913](#)
- c
  - L4::Kobject\_2t< Derived, Base1, Base2, PROTO, S\_DEMAND >, [1291](#)
  - L4::Kobject\_3t< Derived, Base1, Base2, Base3, PROTO, S\_DEMAND >, [1295](#)
- C++ Exceptions, [591](#)
- C++ IPC Interface Definition, [191](#)
- C\_bits
  - cxx::Bitmap\_base, [837](#)
  - L4Re::Util::Bitmap\_base, [1759](#)
- Cache Consistency, [192](#)
  - I4\_cache\_clean\_data, [193](#)



- l4\_cache\_coherent, [194](#)
- l4\_cache\_dma\_coherent, [194](#)
- l4\_cache\_flush\_data, [195](#)
- l4\_cache\_inv\_data, [195](#)
- Cache\_buffered
  - L4Re::Rm::F, [1739](#)
  - Rm::F, [2335](#)
- Cache\_normal
  - L4Re::Rm::F, [1739](#)
  - Rm::F, [2335](#)
- Cache\_uncached
  - L4Re::Rm::F, [1739](#)
  - Rm::F, [2335](#)
- Cacheable
  - L4Re::Dataspace::F, [1616](#)
- Cached
  - L4::lpc::Snd\_fpage, [1186](#)
- Cacheopt
  - L4::lpc::Snd\_fpage, [1186](#)
- Caching\_mask
  - L4Re::Dataspace::F, [1616](#)
  - L4Re::Rm::F, [1739](#)
  - Rm::F, [2334](#)
- Caching\_shift
  - L4Re::Dataspace::F, [1615](#)
  - L4Re::Rm, [1722](#)
  - Rm, [2323](#)
- call
  - L4::Arm\_smccc, [992](#)
  - L4::lpc::lostream, [1121](#)
- Cap
  - L4::Cap< T >, [1006](#)
  - L4::lpc::Cap< T >, [1113](#)
- cap
  - L4::Cap\_base, [1013](#)
  - L4::Invalid\_capability, [1090](#)
  - L4::Kobject, [1285](#)
- cap\_alloc
  - L4Re Capability API, [579](#)
- Cap\_base
  - L4::Cap\_base, [1011](#), [1012](#)
- cap\_cast
  - L4, [736](#), [737](#)
- cap\_dynamic\_cast
  - L4, [738](#)
- cap\_equal
  - L4::Task, [1396](#)
- Cap\_mask
  - L4::lpc::Cap< T >, [1112](#)
- cap\_received
  - L4::lpc::Snd\_fpage, [1189](#)
- cap\_reinterpret\_cast
  - L4, [739](#), [740](#)
- Cap\_type
  - L4::Cap\_base, [1011](#)
- cap\_valid
  - L4::Task, [1397](#)
- Capabilities, [437](#)
- L4\_BASE\_ARM\_SMCCC\_CAP, [439](#)
- L4\_BASE\_CAPS\_LAST, [439](#)
- L4\_BASE\_DEBUGGER\_CAP, [439](#)
- L4\_BASE\_FACTORY\_CAP, [439](#)
- L4\_BASE\_ICU\_CAP, [439](#)
- L4\_BASE\_IOMMU\_CAP, [439](#)
- L4\_BASE\_LOG\_CAP, [439](#)
- L4\_BASE\_PAGER\_CAP, [439](#)
- L4\_BASE\_SCHEDULER\_CAP, [439](#)
- L4\_BASE\_TASK\_CAP, [439](#)
- L4\_BASE\_THREAD\_CAP, [439](#)
- l4\_cap\_idx\_t, [438](#)
- l4\_capability\_equal, [439](#)
- l4\_default\_caps\_t, [439](#)
- l4\_is\_invalid\_cap, [440](#)
- l4\_is\_valid\_cap, [440](#)
- Capabilities and Naming, [23](#)
- capability
  - L4\_DISABLE\_COPY, [3047](#)
- Capability allocator, [559](#)
- l4re\_util\_cap\_last, [560](#)
- Caps
  - L4::Type\_info::Demand\_t< CAPS, FLAGS, MEM, PORTS >, [1443](#)
- caps
  - l4re\_env\_t, [1934](#)
- cast
  - L4vcpu::Vcpu, [2020](#)
- cfg\_read
  - L4vbus::Pci\_dev, [1990](#)
  - L4vbus::Pci\_host\_bridge, [1996](#)
- cfg\_write
  - L4vbus::Pci\_dev, [1990](#)
  - L4vbus::Pci\_host\_bridge, [1996](#)
- change\_mode
  - L4::Uart, [1501](#)
  - L4::Uart\_apb, [1507](#)
- change\_queue\_config
  - L4virtio::Svr::Dev\_config, [2151](#)
- char\_avail
  - L4::Uart, [1501](#)
  - L4::Uart\_apb, [1508](#)
- check\_castable\_from
  - L4::Cap< T >, [1007](#)
- check\_convertible\_from
  - L4::Cap< T >, [1007](#)
- check\_ports
  - Virtio\_switch, [2356](#)
- check\_ready
  - L4Re::Vfs::Be\_file, [1843](#)
  - L4Re::Vfs::Generic\_file, [1867](#)
- check\_size
  - L4::lpc::Msg, [753](#), [754](#)
- chkcap
  - L4Re, [765](#)
- chkipc
  - L4Re, [766](#)
- chksys

- L4Re, 767, 768
- Chunks, 602
  - l4shmc\_add\_chunk, 603
  - l4shmc\_chunk\_capacity, 603
  - l4shmc\_chunk\_ptr, 604
  - l4shmc\_chunk\_signal, 604
  - l4shmc\_get\_chunk, 605
  - l4shmc\_get\_chunk\_to, 605
  - l4shmc\_iterate\_chunk, 606
- clamp
  - Small C++ Template Library, 630
- Class
  - L4::Kobject\_2t< Derived, Base1, Base2, PROTO, S\_DEMAND >, 1291
  - L4::Kobject\_3t< Derived, Base1, Base2, Base3, PROTO, S\_DEMAND >, 1294
- clear
  - cxx::Bits::Basic\_list< POLICY >, 868
  - L4::Types::Flags< BITS\_ENUM, UNDERLYING >, 1480
  - L4drivers::Register\_tmpl< BITS, BLOCK >, 1583
  - L4Re::Dataspace, 1606
  - L4Re::Util::Dataspace\_svr, 1790
  - L4vcpu::State, 2015
- clear\_bit
  - cxx::Bitmap\_base, 842
  - L4Re::Util::Bitmap\_base, 1761
- Coherent
  - L4Re::Dma\_space, 1625
- Color\_component
  - L4Re::Video::Color\_component, 1891
- Com\_error
  - L4::Com\_error, 1024
- Comfortable Command Line Parsing, 710
  - parse\_cmdline, 710
- Compound
  - L4::lpc::Snd\_fpage, 1187
- config\_get
  - L4vbus::Gpio\_pin, 1977
- config\_pad
  - L4vbus::Gpio\_module, 1969
  - L4vbus::Gpio\_pin, 1977
- config\_pull
  - L4vbus::Gpio\_pin, 1978
- config\_queue
  - L4virtio::Device, 2034
  - L4virtio::Driver::Device, 2051
- Cons, the Console Multiplexer, 85
- Console API, 581
- console\_multiport\_bfm\_t
  - L4virtio::Svr::Console::Features, 2120
- Console\_port
  - L4virtio::Svr::Console::Control\_message, 2096
- console\_size\_bfm\_t
  - L4virtio::Svr::Console::Features, 2120
- consts.h
  - L4\_CAP\_SIZE, 3060
  - L4\_SYSF\_CALL, 3060
  - L4\_SYSF\_OPEN\_WAIT, 3061
  - L4\_SYSF\_RECV, 3061
  - L4\_SYSF\_REPLY, 3061
  - L4\_SYSF\_REPLY\_AND\_WAIT, 3061
  - L4\_SYSF\_SEND, 3062
  - L4\_SYSF\_SEND\_AND\_WAIT, 3062
  - L4\_SYSF\_WAIT, 3062
- consumed
  - L4virtio::Svr::Virtqueue, 2259
- Consumer, 610, 619
  - l4shmc\_chunk\_consumed, 611
  - l4shmc\_chunk\_size, 611
  - l4shmc\_chunk\_try\_to\_take\_for\_reading, 611
  - l4shmc\_enable\_chunk, 612
  - l4shmc\_enable\_signal, 620
  - l4shmc\_is\_chunk\_ready, 612
  - l4shmc\_wait\_any, 620
  - l4shmc\_wait\_any\_to, 620
  - l4shmc\_wait\_any\_try, 621
  - l4shmc\_wait\_chunk, 613
  - l4shmc\_wait\_chunk\_to, 613
  - l4shmc\_wait\_chunk\_try, 614
  - l4shmc\_wait\_signal, 621
  - l4shmc\_wait\_signal\_to, 622
  - l4shmc\_wait\_signal\_try, 622
- contains
  - L4virtio::Svr::Driver\_mem\_region\_t< DATA >, 2181
- Continue
  - L4::lpc::Snd\_fpage, 1186
- Continuous
  - L4Re::Mem\_alloc, 1685
- contrib/libio-io/l4/io/io.h, 2555, 2557
- contrib/libio-io/l4/io/types.h, 3268
- control
  - L4::Thread, 1407
- Conventional
  - L4::Kip::Mem\_desc, 1276
- copy
  - L4::Cap< T >, 1007
  - L4::Cap\_base, 1014
  - L4Re::Util::Dataspace\_svr, 1790
- copy\_in
  - L4Re::Dataspace, 1607
- copy\_pkt
  - Virtio\_vlan\_mangle, 2359
- copy\_receive\_cap
  - L4Re::Util::Names::Name\_space, 1814
- copy\_to
  - L4virtio::Svr::Data\_buffer, 2145
- count
  - L4::Kip::Mem\_desc, 1278, 1279
- Counting\_cap\_alloc
  - L4Re::Util::Counting\_cap\_alloc< COUNTER-TYPE, Dbg >, 1783
- CPU related functions, 642
  - l4util\_cpu\_capabilities, 643
  - l4util\_cpu\_capabilities\_nocheck, 643

- l4util\_cpu\_has\_cpuid, [644](#)
- cpu\_allow\_shutdown
  - L4::Platform\_control, [1326](#)
- cpu\_disable
  - L4::Platform\_control, [1326](#)
- cpu\_enable
  - L4::Platform\_control, [1327](#)
- create
  - L4::Factory, [1059](#), [1060](#)
- create\_buffer
  - L4Re::Video::Goos, [1899](#)
- create\_factory
  - L4::Factory, [1061](#)
- create\_gate
  - L4::Factory, [1063](#)
- create\_task
  - L4::Factory, [1064](#)
- create\_thread\_group
  - L4::Factory, [1065](#)
- create\_view
  - L4Re::Video::Goos, [1899](#)
- cur\_buf
  - Net\_transfer, [2317](#)
- current\_flags
  - L4virtio::Svr::Request\_processor, [2186](#)
- cx
  - l4\_vcpu\_regs\_t, [1555](#)
- cxx, [723](#)
  - access\_once, [726](#)
  - gcd, [726](#)
  - lcm, [727](#)
  - write\_now, [728](#)
- cxx::arith::Ld< V >, [787](#)
- cxx::Avl\_map< KEY\_TYPE, DATA\_TYPE, COMPARE, ALLOC >, [788](#)
  - Avl\_map, [792](#)
  - emplace, [792](#)
  - insert, [792](#)
  - operator[], [793](#), [794](#)
- cxx::Avl\_set< ITEM\_TYPE, COMPARE, ALLOC >, [794](#)
- cxx::Avl\_tree< Node, Get\_key, Compare >, [798](#)
  - insert, [804](#)
  - Iterator, [804](#)
  - remove, [804](#)
- cxx::Avl\_tree\_node, [806](#)
- cxx::Base\_slab< Obj\_size, Slab\_size, Max\_free, Alloc >, [808](#)
  - alloc, [811](#)
  - free, [811](#)
  - free\_objects, [811](#)
  - max\_free\_slabs, [811](#)
  - object\_size, [811](#)
  - objects\_per\_slab, [811](#)
  - slab\_size, [811](#)
  - total\_objects, [812](#)
- cxx::Base\_slab< Obj\_size, Slab\_size, Max\_free, Alloc >::Slab\_i, [812](#)
- cxx::Base\_slab\_static< Obj\_size, Slab\_size, Max\_free, Alloc >, [813](#)
  - alloc, [816](#)
  - free, [816](#)
  - free\_objects, [817](#)
  - max\_free\_slabs, [816](#)
  - object\_size, [816](#)
  - objects\_per\_slab, [816](#)
  - slab\_size, [816](#)
  - total\_objects, [817](#)
- cxx::Bitfield< T, LSB, MSB >, [818](#)
  - Bits, [821](#)
  - Bits\_type, [820](#)
  - get, [821](#)
  - get\_unshifted, [821](#)
  - Lsb, [821](#)
  - Msb, [821](#)
  - set, [821](#)
  - set\_dirty, [822](#)
  - set\_unshifted, [823](#)
  - set\_unshifted\_dirty, [823](#)
  - Shift\_type, [820](#)
  - val, [824](#)
  - val\_dirty, [824](#)
  - val\_unshifted, [825](#)
- cxx::Bitfield< T, LSB, MSB >::Value< TT >, [826](#)
- cxx::Bitfield< T, LSB, MSB >::Value\_base< TT >, [827](#)
- cxx::Bitfield< T, LSB, MSB >::Value\_unshifted< TT >, [828](#)
- cxx::Bitmap< BITS >, [830](#)
  - scan\_zero, [833](#)
- cxx::Bitmap\_base, [834](#)
  - atomic\_clear\_bit, [837](#)
  - atomic\_get\_and\_clear, [837](#)
  - atomic\_get\_and\_set, [838](#)
  - atomic\_set\_bit, [838](#)
  - bit, [839](#), [840](#)
  - bit\_index, [841](#)
  - C\_bits, [837](#)
  - clear\_bit, [842](#)
  - operator[], [842](#), [843](#)
  - scan\_zero, [844](#)
  - set\_bit, [845](#)
  - W\_bits, [837](#)
  - word\_index, [845](#)
- cxx::Bitmap\_base::Bit, [847](#)
- cxx::Bitmap\_base::Char< BITS >, [847](#)
- cxx::Bitmap\_base::Word< BITS >, [848](#)
- cxx::Bits, [729](#)
- cxx::Bits::Avl\_map\_get\_key< KEY\_TYPE >, [849](#)
- cxx::Bits::Avl\_set\_get\_key< KEY\_TYPE >, [850](#)
- cxx::Bits::Avl\_set\_iter< Node, Key, Node\_op >, [850](#)
  - Avl\_set\_iter, [852](#)
  - operator->, [853](#)
  - operator\*, [853](#)
- cxx::Bits::Base\_avl\_set< ITEM\_TYPE, COMPARE, ALLOC, GET\_KEY >, [854](#)
  - Base\_avl\_set, [857](#)

- begin, [858](#)
- E\_exist, [857](#)
- E\_inval, [857](#)
- E\_noent, [857](#)
- E\_nomem, [857](#)
- emplace, [858](#)
- end, [859](#)
- erase, [860](#)
- find\_node, [860](#)
- insert, [860](#)
- lower\_bound\_node, [861](#)
- operator=, [862](#)
- rbegin, [862](#)
- remove, [862](#)
- rend, [863](#)
- cxx::Bits::Base\_avl\_set< ITEM\_TYPE, COMPARE, ALLOC, GET\_KEY >::Node, [864](#)
- operator->, [865](#)
- operator\*, [865](#)
- valid, [865](#)
- cxx::Bits::Basic\_list< POLICY >, [866](#)
- clear, [868](#)
- iter, [868](#)
- cxx::Bits::Bst< Node, Get\_key, Compare >, [869](#)
- begin, [872](#), [873](#)
- dir, [873](#), [874](#)
- end, [875](#)
- find, [876](#)
- find\_node, [876](#)
- lower\_bound\_node, [877](#)
- rbegin, [878](#)
- remove\_all, [879](#)
- remove\_tree, [880](#)
- rend, [881](#)
- cxx::Bits::Bst\_node, [882](#)
- cxx::Bits::Direction, [884](#)
- Direction\_e, [885](#)
- L, [885](#)
- N, [885](#)
- operator!, [886](#)
- R, [885](#)
- cxx::Bits::Smart\_ptr\_list< ITEM >, [886](#)
- pop\_front, [889](#)
- cxx::Bits::Smart\_ptr\_list\_item< T, STORE\_T >, [889](#)
- cxx::Elide\_dtor< T >, [891](#)
- cxx::H\_list< T, POLICY >, [892](#)
- erase, [895](#)
- insert, [895](#)
- insert\_after, [896](#)
- insert\_before, [896](#)
- iter, [897](#)
- pop\_front, [897](#)
- remove, [898](#)
- replace, [898](#)
- cxx::H\_list\_item\_t< ELEM\_TYPE >, [899](#)
- ~H\_list\_item\_t, [901](#)
- H\_list\_item\_t, [901](#)
- cxx::H\_list\_t< T >, [902](#)
- cxx::List< D, Alloc >, [906](#)
- operator[], [907](#)
- cxx::List< D, Alloc >::Iter, [908](#)
- cxx::List\_alloc, [909](#)
- alloc, [910](#)
- alloc\_max, [910](#)
- avail, [911](#)
- free, [912](#)
- List\_alloc, [910](#)
- cxx::List\_item, [913](#)
- push\_back, [914](#)
- push\_front, [914](#)
- remove, [915](#)
- cxx::List\_item::Iter, [916](#)
- cxx::List\_item::T\_iter< T, Poly >, [918](#)
- cxx::Lt\_functor< Obj >, [920](#)
- cxx::New\_allocator< \_Type >, [920](#)
- cxx::Nothrow, [922](#)
- cxx::Pair< First, Second >, [922](#)
- Pair, [925](#)
- cxx::Pair\_first\_compare< Cmp, Typ >, [925](#)
- operator(), [927](#)
- Pair\_first\_compare, [926](#)
- cxx::Ref\_obj\_list\_item< T >, [927](#)
- cxx::Ref\_ptr< T, CNT >, [929](#)
- get, [933](#)
- ptr, [933](#)
- Ref\_ptr, [932](#)
- release, [933](#)
- cxx::S\_list< T, POLICY >, [934](#)
- pop\_front, [937](#)
- cxx::Slab< Type, Slab\_size, Max\_free, Alloc >, [937](#)
- alloc, [940](#)
- free, [941](#)
- cxx::Slab\_static< Type, Slab\_size, Max\_free, Alloc >, [942](#)
- alloc, [945](#)
- cxx::static\_vector< T, IDX >, [946](#)
- cxx::String, [947](#)
- find, [951](#)
- from\_dec, [952](#)
- from\_hex, [953](#)
- starts\_with, [954](#)
- String, [951](#)
- cxx::Weak\_ref< T >, [955](#)
- cxx::Weak\_ref\_base, [957](#)
- cxx::Weak\_ref\_base::List, [960](#)
- d\_tag
- Elf32\_Dyn, [966](#)
- Elf64\_Dyn, [976](#)
- data
- L4::lpc::Varg, [1196](#)
- Data\_buffer
- L4virtio::Svr::Data\_buffer, [2144](#)
- data\_size
- L4virtio::Svr::Block\_request< Ds\_data >, [2094](#)
- data\_space
- L4Re::Vfs::Be\_file, [1843](#)

- L4Re::Vfs::Regular\_file, [1880](#)
- Dataspace interface, [518](#)
  - l4re\_ds\_allocate, [520](#)
  - l4re\_ds\_clear, [520](#)
  - l4re\_ds\_copy\_in, [521](#)
  - L4RE\_DS\_F\_BUFFERABLE, [519](#)
  - L4RE\_DS\_F\_CACHEABLE, [519](#)
  - L4RE\_DS\_F\_CACHING\_MASK, [519](#)
  - L4RE\_DS\_F\_CACHING\_SHIFT, [519](#)
  - L4RE\_DS\_F\_NORMAL, [519](#)
  - L4RE\_DS\_F\_UNCACHEABLE, [519](#)
  - l4re\_ds\_flags, [521](#)
  - l4re\_ds\_info, [522](#)
  - l4re\_ds\_map\_flags, [519](#)
  - l4re\_ds\_map\_info, [522](#)
  - l4re\_ds\_size, [523](#)
- dbg\_events
  - L4Re::Env, [1633](#)
- debug
  - L4Re::Debug\_obj, [1620](#)
- Debug interface, [524](#)
  - l4re\_debug\_obj\_debug, [524](#)
- debugger.h
  - L4\_DEBUGGER\_GLOBAL\_ID\_GET\_NAME\_OP, [3136](#)
  - L4\_DEBUGGER\_KOBJ\_GET\_GLOBAL\_ID\_OP, [3135](#)
  - L4\_DEBUGGER\_KOBJ\_GET\_NAME\_OP, [3136](#)
  - L4\_DEBUGGER\_KOBJ\_PTR\_GET\_GLOBAL\_ID\_OP, [3135](#)
  - L4\_DEBUGGER\_KOBJ\_SET\_NAME\_OP, [3135](#)
  - L4\_DEBUGGER\_LOG\_QUERY\_NAME\_OP, [3136](#)
  - L4\_DEBUGGER\_LOG\_QUERY\_TYPEID\_OP, [3135](#)
  - L4\_DEBUGGER\_LOG\_SWITCH\_OP, [3135](#)
  - L4\_DEBUGGER\_OBJ\_INFO\_OP, [3136](#)
  - L4\_DEBUGGER\_TASK\_ADD\_IMAGE\_INFO\_OP, [3136](#)
- Debugging API, [581](#)
- dec
  - L4Re::Util::Counter< COUNTER >, [1779](#)
  - L4Re::Util::Counter\_atomic< COUNTER >, [1781](#)
- dec\_refcnt
  - L4::Kobject, [1287](#)
- declval
  - L4::Types, [760](#)
- Dedicated
  - L4::Kip::Mem\_desc, [1276](#)
- delete\_buffer
  - L4Re::Video::Goos, [1900](#)
- delete\_obj
  - L4::Task, [1398](#)
- delete\_view
  - L4Re::Video::Goos, [1901](#)
- Demand
  - L4::Kobject\_typeid< T >, [1299](#)
  - L4::Type\_info::Demand, [1439](#)
- demand
  - L4::Kobject\_typeid< T >, [1300](#)
  - L4::Kobject\_typeid< void >, [1303](#)
- Deprecated List, [95](#)
- desc
  - L4virtio::Driver::Virtqueue, [2074](#)
  - L4virtio::Svr::Virtqueue, [2260](#)
  - L4virtio::Svr::Virtqueue::Head\_desc, [2268](#)
- desc\_align
  - L4virtio::Virtqueue, [2275](#)
- desc\_avail
  - L4virtio::Svr::Virtqueue, [2261](#)
- desc\_size
  - L4virtio::Virtqueue, [2275](#)
- detach
  - L4::Irq, [1259](#)
  - L4Re::Rm, [1726–1728](#)
  - L4Re::Util::Event\_buffer\_t< PAYLOAD >, [1801](#)
  - Rm, [2326](#), [2327](#)
- Detach\_again
  - L4Re::Rm, [1722](#)
  - Rm, [2323](#)
- Detach\_exact
  - L4Re::Rm, [1721](#)
  - Rm, [2322](#)
- Detach\_flags
  - L4Re::Rm, [1721](#)
  - Rm, [2322](#)
- Detach\_free
  - L4Re::Rm::F, [1739](#)
  - Rm::F, [2334](#)
- Detach\_keep
  - L4Re::Rm, [1721](#)
  - Rm, [2322](#)
- Detach\_overlap
  - L4Re::Rm, [1721](#)
  - Rm, [2322](#)
- Detach\_result
  - L4Re::Rm, [1721](#)
  - Rm, [2322](#)
- Detached\_ds
  - L4Re::Rm, [1722](#)
  - Rm, [2323](#)
- Dev\_config
  - L4virtio::Svr::Dev\_config, [2149](#), [2150](#)
- dev\_handle
  - L4vbus::Device, [1960](#)
- Device
  - L4vbus::Device, [1959](#)
  - L4virtio::Svr::Console::Device, [2103](#), [2104](#)
- device
  - L4vbus::Device, [1960](#)
- Device\_add
  - L4virtio::Svr::Console::Control\_message, [2096](#)
- device\_by\_hid
  - L4vbus::Device, [1961](#)
- device\_config
  - L4virtio::Device, [2034](#)
- device\_error

- L4virtio::Svr::Device\_t< DATA >, 2169
- device\_notification\_irq
  - L4virtio::Device, 2035
- device\_notify\_irq
  - L4virtio::Svr::Device\_t< DATA >, 2169
- Device\_ready
  - L4virtio::Svr::Console::Control\_message, 2096
- Device\_remove
  - L4virtio::Svr::Console::Control\_message, 2096
- DF\_1\_CONFALT
  - ELF binary format, 693
- DF\_1\_DIRECT
  - ELF binary format, 693
- DF\_1\_DISPRELDNE
  - ELF binary format, 693
- DF\_1\_DISPRELPND
  - ELF binary format, 693
- DF\_1\_ENDFILTEE
  - ELF binary format, 693
- DF\_1\_GLOBAL
  - ELF binary format, 693
- DF\_1\_GROUP
  - ELF binary format, 693
- DF\_1\_INITFIRST
  - ELF binary format, 693
- DF\_1\_INTERPOSE
  - ELF binary format, 693
- DF\_1\_LOADFLTR
  - ELF binary format, 693
- DF\_1\_NODEFLIB
  - ELF binary format, 693
- DF\_1\_NODELETE
  - ELF binary format, 693
- DF\_1\_NODUMP
  - ELF binary format, 693
- DF\_1\_NOOPEN
  - ELF binary format, 693
- DF\_1\_NOW
  - ELF binary format, 693
- DF\_1\_ORIGIN
  - ELF binary format, 693
- DF\_BIND\_NOW
  - ELF binary format, 694
- DF\_ORIGIN
  - ELF binary format, 694
- DF\_P1\_GROUPPERM
  - ELF binary format, 693
- DF\_P1\_LAZYLOAD
  - ELF binary format, 693
- DF\_STATIC\_TLS
  - ELF binary format, 694
- DF\_SYMBOLIC
  - ELF binary format, 694
- DF\_TEXTREL
  - ELF binary format, 694
- df1
  - l4\_vm\_vmx\_vcpu\_infos\_t, 1565
- di
  - l4\_vcpu\_regs\_t, 1555
- dir
  - cxx::Bits::Bst< Node, Get\_key, Compare >, 873, 874
- Direction
  - L4Re::Dma\_space, 1625
- Direction\_e
  - cxx::Bits::Direction, 885
- disable
  - L4virtio::Virtqueue, 2276
- disable\_notify
  - L4virtio::Svr::Virtqueue, 2262
- disassociate
  - L4Re::Dma\_space, 1626
- dispatch
  - L4::Basic\_registry, 997
  - L4::Epiface, 1042
  - L4::Epiface\_t< Derived, IFACE, BASE, bool >, 1049
  - L4::Irqp\_t< Derived, BASE, bool >, 1272
  - L4::Server\_object, 1375, 1376
- dispatch\_meta\_request
  - L4::Server\_object\_t< IFACE, BASE >, 1381
- DMA space, 280
- DMA Space Interface, 525
  - l4re\_dma\_space\_associate, 526
  - l4re\_dma\_space\_disassociate, 527
  - l4re\_dma\_space\_map, 527
  - l4re\_dma\_space\_t, 526
  - l4re\_dma\_space\_unmap, 528
- dma\_space.h
  - L4RE\_DMA\_SPACE\_BIDIRECTIONAL, 2813
  - L4RE\_DMA\_SPACE\_COHERENT, 2814
  - l4re\_dma\_space\_direction, 2813
  - L4RE\_DMA\_SPACE\_FROM\_DEVICE, 2813
  - L4RE\_DMA\_SPACE\_NONE, 2813
  - L4RE\_DMA\_SPACE\_PHYS\_SPACE, 2814
  - l4re\_dma\_space\_space\_attribs, 2813
  - L4RE\_DMA\_SPACE\_TO\_DEVICE, 2813
- done
  - L4virtio::Svr::Data\_buffer, 2145
  - Net\_transfer, 2317
- down
  - L4::Semaphore, 1364
- driver\_acknowledge
  - L4virtio::Driver::Device, 2051
- driver\_connect
  - L4virtio::Driver::Device, 2052
- Driver\_mem\_region\_t
  - L4virtio::Svr::Driver\_mem\_region\_t< DATA >, 2181
- drop\_requests
  - L4virtio\_port, 2311
  - Virtio\_net\_request, 2351
- drv\_base
  - L4virtio::Svr::Driver\_mem\_region\_t< DATA >, 2182
- ds

- L4virtio::Svr::Dev\_config, [2152](#)
- L4virtio::Svr::Driver\_mem\_region\_t< DATA >, [2182](#)
- Ds\_map\_mask
  - L4Re::Rm::F, [1739](#)
  - Rm::F, [2335](#)
- ds\_offset
  - L4virtio::Svr::Driver\_mem\_region\_t< DATA >, [2182](#)
- DT\_BIND\_NOW
  - ELF binary format, [695](#)
- DT\_DEBUG
  - ELF binary format, [695](#)
- DT\_ENCODING
  - ELF binary format, [695](#)
- DT\_FINI
  - ELF binary format, [694](#)
- DT\_FINI\_ARRAY
  - ELF binary format, [695](#)
- DT\_FINI\_ARRAYSZ
  - ELF binary format, [695](#)
- DT\_FLAGS
  - ELF binary format, [695](#)
- DT\_HASH
  - ELF binary format, [694](#)
- DT\_HIOS
  - ELF binary format, [695](#)
- DT\_HIPROC
  - ELF binary format, [695](#)
- DT\_INIT
  - ELF binary format, [694](#)
- DT\_INIT\_ARRAY
  - ELF binary format, [695](#)
- DT\_INIT\_ARRAYSZ
  - ELF binary format, [695](#)
- DT\_JMPREL
  - ELF binary format, [695](#)
- DT\_LOOS
  - ELF binary format, [695](#)
- DT\_LOPROC
  - ELF binary format, [695](#)
- DT\_NEEDED
  - ELF binary format, [694](#)
- DT\_NULL
  - ELF binary format, [694](#)
- DT\_NUM
  - ELF binary format, [695](#)
- DT\_PLTGOT
  - ELF binary format, [694](#)
- DT\_PLTRELSZ
  - ELF binary format, [694](#)
- DT\_PREINIT\_ARRAY
  - ELF binary format, [695](#)
- DT\_PREINIT\_ARRAYSZ
  - ELF binary format, [695](#)
- DT\_PTRREL
  - ELF binary format, [695](#)
- DT\_REL
  - ELF binary format, [695](#)
- DT\_RELA
  - ELF binary format, [694](#)
- DT\_RELAENT
  - ELF binary format, [694](#)
- DT\_RELASZ
  - ELF binary format, [694](#)
- DT\_RELENT
  - ELF binary format, [695](#)
- DT\_RELSZ
  - ELF binary format, [695](#)
- DT\_RPATH
  - ELF binary format, [694](#)
- DT\_RUNPATH
  - ELF binary format, [695](#)
- DT\_SONAME
  - ELF binary format, [694](#)
- DT\_STRSZ
  - ELF binary format, [694](#)
- DT\_STRTAB
  - ELF binary format, [694](#)
- DT\_SYMBOLIC
  - ELF binary format, [694](#)
- DT\_SYMENT
  - ELF binary format, [694](#)
- DT\_SYMTAB
  - ELF binary format, [694](#)
- DT\_TEXTREL
  - ELF binary format, [695](#)
- dump
  - L4Re::Video::Color\_component, [1891](#)
  - L4Re::Video::Pixel\_info, [1914](#)
  - L4virtio::Virtqueue, [2277](#)
- dx
  - l4\_vcpu\_regs\_t, [1555](#)
- E\_exist
  - cxx::Bits::Base\_avl\_set< ITEM\_TYPE, COM-PARE, ALLOC, GET\_KEY >, [857](#)
- e\_flags
  - Elf32\_Ehdr, [967](#)
  - Elf64\_Ehdr, [978](#)
- E\_inval
  - cxx::Bits::Base\_avl\_set< ITEM\_TYPE, COM-PARE, ALLOC, GET\_KEY >, [857](#)
- e\_machine
  - Elf32\_Ehdr, [967](#)
  - Elf64\_Ehdr, [978](#)
- E\_noent
  - cxx::Bits::Base\_avl\_set< ITEM\_TYPE, COM-PARE, ALLOC, GET\_KEY >, [857](#)
- E\_nomem
  - cxx::Bits::Base\_avl\_set< ITEM\_TYPE, COM-PARE, ALLOC, GET\_KEY >, [857](#)
- e\_type
  - Elf32\_Ehdr, [968](#)
  - Elf64\_Ehdr, [978](#)
- e\_version
  - Elf32\_Ehdr, [968](#)

- Elf64\_Ehdr, 979
- Eager\_map
  - L4Re::Rm::F, 1738
  - Rm::F, 2334
- EDID parsing functionality, 446
  - libedid\_block\_size, 447
  - libedid\_check\_header, 447
  - libedid\_checksum, 447
  - libedid\_consts, 446
  - libedid\_dump, 447
  - libedid\_dump\_standard\_timings, 448
  - libedid\_num\_ext\_blocks, 448
  - libedid\_pnp\_id, 448
  - libedid\_prefered\_resolution, 449
  - libedid\_revision, 449
  - libedid\_version, 449
- EF\_ARM\_ALIGN8
  - ELF binary format, 695
- EI\_ABIVERSION
  - ELF binary format, 696
- EI\_CLASS
  - ELF binary format, 696
- EI\_DATA
  - ELF binary format, 696
- EI\_MAG0
  - ELF binary format, 696
- EI\_MAG1
  - ELF binary format, 696
- EI\_MAG2
  - ELF binary format, 696
- EI\_MAG3
  - ELF binary format, 696
- EI\_NIDENT
  - ELF binary format, 691
- EI\_OSABI
  - ELF binary format, 696
- EI\_PAD
  - ELF binary format, 696
- EI\_VERSION
  - ELF binary format, 696
- ELF binary format, 683
  - AT\_BASE, 691
  - AT\_EGID, 692
  - AT\_ENTRY, 691
  - AT\_EUID, 692
  - AT\_EXECD, 691
  - AT\_FLAGS, 691
  - AT\_GID, 692
  - AT\_IGNORE, 691
  - AT\_L4\_AUX, 692
  - AT\_L4\_ENV, 692
  - AT\_L4\_KIP, 692
  - AT\_NOTELF, 691
  - AT\_NULL, 691
  - AT\_PAGESZ, 691
  - AT\_PHDR, 691
  - AT\_PHENT, 691
  - AT\_PHNUM, 691
  - AT\_UID, 691
  - DF\_1\_CONFALT, 693
  - DF\_1\_DIRECT, 693
  - DF\_1\_DISPRELDNE, 693
  - DF\_1\_DISPRELPND, 693
  - DF\_1\_ENDFILTEE, 693
  - DF\_1\_GLOBAL, 693
  - DF\_1\_GROUP, 693
  - DF\_1\_INITFIRST, 693
  - DF\_1\_INTERPOSE, 693
  - DF\_1\_LOADFLTR, 693
  - DF\_1\_NODEFLIB, 693
  - DF\_1\_NODELETE, 693
  - DF\_1\_NODUMP, 693
  - DF\_1\_NOOPEN, 693
  - DF\_1\_NOW, 693
  - DF\_1\_ORIGIN, 693
  - DF\_BIND\_NOW, 694
  - DF\_ORIGIN, 694
  - DF\_P1\_GROUPPER, 693
  - DF\_P1\_LAZYLOAD, 693
  - DF\_STATIC\_TLS, 694
  - DF\_SYMBOLIC, 694
  - DF\_TEXTREL, 694
  - DT\_BIND\_NOW, 695
  - DT\_DEBUG, 695
  - DT\_ENCODING, 695
  - DT\_FINI, 694
  - DT\_FINI\_ARRAY, 695
  - DT\_FINI\_ARRAYSZ, 695
  - DT\_FLAGS, 695
  - DT\_HASH, 694
  - DT\_HIOS, 695
  - DT\_HIPROC, 695
  - DT\_INIT, 694
  - DT\_INIT\_ARRAY, 695
  - DT\_INIT\_ARRAYSZ, 695
  - DT\_JMPREL, 695
  - DT\_LOOS, 695
  - DT\_LOPROC, 695
  - DT\_NEEDED, 694
  - DT\_NULL, 694
  - DT\_NUM, 695
  - DT\_PLTGOT, 694
  - DT\_PLTRELSZ, 694
  - DT\_PREINIT\_ARRAY, 695
  - DT\_PREINIT\_ARRAYSZ, 695
  - DT\_PTRREL, 695
  - DT\_REL, 695
  - DT\_RELA, 694
  - DT\_RELAENT, 694
  - DT\_RELASZ, 694
  - DT\_RELENT, 695
  - DT\_RELSZ, 695
  - DT\_RPATH, 694
  - DT\_RUNPATH, 695
  - DT\_SONAME, 694
  - DT\_STRSZ, 694



DT\_STRTAB, [694](#)  
DT\_SYMBOLIC, [694](#)  
DT\_SYMENT, [694](#)  
DT\_SYMTAB, [694](#)  
DT\_TEXTREL, [695](#)  
EF\_ARM\_ALIGN8, [695](#)  
EI\_ABIVERSION, [696](#)  
EI\_CLASS, [696](#)  
EI\_DATA, [696](#)  
EI\_MAG0, [696](#)  
EI\_MAG1, [696](#)  
EI\_MAG2, [696](#)  
EI\_MAG3, [696](#)  
EI\_NIDENT, [691](#)  
EI\_OSABI, [696](#)  
EI\_PAD, [696](#)  
EI\_VERSION, [696](#)  
ELF32\_R\_TYPE, [689](#)  
ELF32\_ST\_BIND, [689](#)  
ELF32\_ST\_TYPE, [689](#)  
ELF64\_R\_TYPE, [689](#)  
ELF64\_ST\_BIND, [690](#)  
ELF64\_ST\_TYPE, [690](#)  
Elf\_ARM\_SBs, [691](#)  
Elf\_ATs, [691](#)  
Elf\_CLASSs, [692](#)  
Elf\_DATAs, [692](#)  
Elf\_DF\_1s, [692](#)  
Elf\_DF\_P1s, [693](#)  
Elf\_DFs, [693](#)  
Elf\_DTs, [694](#)  
Elf\_EF\_ARM\_s, [695](#)  
Elf\_EIs, [695](#)  
Elf\_EMs, [696](#)  
Elf\_ETs, [698](#)  
Elf\_EVs, [698](#)  
Elf\_MAGs, [699](#)  
Elf\_NTs\_core, [699](#)  
Elf\_NTs\_obj, [700](#)  
Elf\_OSABIs, [700](#)  
ELF\_PFs, [700](#)  
Elf\_PTs, [701](#)  
Elf\_R\_386\_s, [701](#)  
Elf\_R\_AARCH64\_s, [702](#)  
Elf\_R\_ARM\_s, [703](#)  
Elf\_R\_X86\_64\_s, [703](#)  
Elf\_SHF\_s\_ARM, [704](#)  
Elf\_SHFs, [705](#)  
Elf\_SHNs, [705](#)  
Elf\_SHTs, [705](#)  
Elf\_STBs, [706](#)  
Elf\_STTs, [707](#)  
ELFCLASS32, [692](#)  
ELFCLASS64, [692](#)  
ELFCLASSNONE, [692](#)  
ELFCLASSNUM, [692](#)  
ELFDATA2LSB, [692](#)  
ELFDATA2MSB, [692](#)  
ELFDATANONE, [692](#)  
ELFDATANUM, [692](#)  
ELFMAG0, [699](#)  
ELFMAG1, [699](#)  
ELFMAG2, [699](#)  
ELFMAG3, [699](#)  
ELFOSABI\_AIX, [700](#)  
ELFOSABI\_ARM, [700](#)  
ELFOSABI\_FREEBSD, [700](#)  
ELFOSABI\_HPUX, [700](#)  
ELFOSABI\_IRIX, [700](#)  
ELFOSABI\_LINUX, [700](#)  
ELFOSABI\_MODESTO, [700](#)  
ELFOSABI\_NETBSD, [700](#)  
ELFOSABI\_NONE, [700](#)  
ELFOSABI\_OPENBSD, [700](#)  
ELFOSABI\_SOLARIS, [700](#)  
ELFOSABI\_STANDALONE, [700](#)  
ELFOSABI\_SYSV, [700](#)  
ELFOSABI\_TRU64, [700](#)  
EM\_386, [696](#)  
EM\_68HC05, [697](#)  
EM\_68HC08, [697](#)  
EM\_68HC11, [697](#)  
EM\_68HC12, [697](#)  
EM\_68HC16, [697](#)  
EM\_68K, [696](#)  
EM\_860, [696](#)  
EM\_88K, [696](#)  
EM\_960, [696](#)  
EM\_AARCH64, [698](#)  
EM\_ALPHA, [697](#)  
EM\_ALTERA\_NIOS2, [698](#)  
EM\_ARC, [697](#)  
EM\_ARC\_A5, [698](#)  
EM\_ARM, [697](#)  
EM\_AVR, [697](#)  
EM\_COLDFIRE, [697](#)  
EM\_CRIS, [697](#)  
EM\_D10V, [697](#)  
EM\_D30V, [697](#)  
EM\_FIREPATH, [697](#)  
EM\_FR20, [697](#)  
EM\_FR30, [697](#)  
EM\_FX66, [697](#)  
EM\_H8\_300, [697](#)  
EM\_H8\_300H, [697](#)  
EM\_H8\_500, [697](#)  
EM\_H8S, [697](#)  
EM\_HUANY, [697](#)  
EM\_IA\_64, [697](#)  
EM\_JAVELIN, [697](#)  
EM\_M32, [696](#)  
EM\_M32R, [698](#)  
EM\_MICROBLAZE, [698](#)  
EM\_MIPS, [696](#)  
EM\_MIPS\_RS4\_BE, [696](#)  
EM\_MIPS\_X, [697](#)

EM\_MMIX, [697](#)  
EM\_MN10200, [698](#)  
EM\_MN10300, [698](#)  
EM\_NONE, [696](#)  
EM\_OPENRISC, [698](#)  
EM\_PARISC, [696](#)  
EM\_PDSP, [697](#)  
EM\_PJ, [698](#)  
EM\_PPC, [697](#)  
EM\_PRISM, [697](#)  
EM\_RCE, [697](#)  
EM\_RH32, [697](#)  
EM\_RISCV, [698](#)  
EM\_SH, [697](#)  
EM\_SPARC, [696](#)  
EM\_SPARC32PLUS, [696](#)  
EM\_SPARC64, [696](#)  
EM\_SPARCV9, [697](#)  
EM\_ST19, [697](#)  
EM\_ST7, [697](#)  
EM\_ST9PLUS, [697](#)  
EM\_SVX, [697](#)  
EM\_TILEGX, [698](#)  
EM\_TILEPRO, [698](#)  
EM\_TRICORE, [697](#)  
EM\_V800, [697](#)  
EM\_V850, [698](#)  
EM\_VAX, [697](#)  
EM\_VPP500, [696](#)  
EM\_X86\_64, [697](#)  
EM\_XTENSA, [698](#)  
EM\_ZSP, [697](#)  
ET\_CORE, [698](#)  
ET\_DYN, [698](#)  
ET\_EXEC, [698](#)  
ET\_HIPROC, [698](#)  
ET\_LOPROC, [698](#)  
ET\_NONE, [698](#)  
ET\_REL, [698](#)  
EV\_CURRENT, [699](#)  
EV\_NONE, [699](#)  
NT\_ASRS, [699](#)  
NT\_AUXV, [699](#)  
NT\_FPREGSET, [699](#)  
NT\_GWINDOWS, [699](#)  
NT\_LWPSINFO, [700](#)  
NT\_LWPSTATUS, [700](#)  
NT\_PLATFORM, [699](#)  
NT\_PRCRED, [700](#)  
NT\_PRFPXREG, [700](#)  
NT\_PRPSINFO, [699](#)  
NT\_PRSTATUS, [699](#)  
NT\_PRXREG, [699](#)  
NT\_PSINFO, [699](#)  
NT\_PSTATUS, [699](#)  
NT\_TASKSTRUCT, [699](#)  
NT\_UTSNAME, [700](#)  
NT\_VERSION, [700](#)  
PF\_ARM\_SB, [691](#)  
PF\_MASKOS, [701](#)  
PF\_MASKPROC, [701](#)  
PF\_R, [701](#)  
PF\_W, [701](#)  
PF\_X, [701](#)  
PT\_DYNAMIC, [701](#)  
PT\_GNU\_EH\_FRAME, [701](#)  
PT\_GNU\_RELRO, [701](#)  
PT\_GNU\_STACK, [701](#)  
PT\_HIOS, [701](#)  
PT\_HIPROC, [701](#)  
PT\_INTERP, [701](#)  
PT\_L4\_AUX, [701](#)  
PT\_L4\_STACK, [701](#)  
PT\_LOAD, [701](#)  
PT\_LOOS, [701](#)  
PT\_LOPROC, [701](#)  
PT\_NOTE, [701](#)  
PT\_NULL, [701](#)  
PT\_NUM, [701](#)  
PT\_PHDR, [701](#)  
PT\_SHLIB, [701](#)  
PT\_TLS, [701](#)  
R\_386\_32, [702](#)  
R\_386\_COPY, [702](#)  
R\_386\_GLOB\_DAT, [702](#)  
R\_386\_GOT32, [702](#)  
R\_386\_GOTOFF, [702](#)  
R\_386\_GOTPC, [702](#)  
R\_386\_JMP\_SLOT, [702](#)  
R\_386\_NONE, [702](#)  
R\_386\_NUM, [702](#)  
R\_386\_PC32, [702](#)  
R\_386\_PLT32, [702](#)  
R\_386\_RELATIVE, [702](#)  
R\_386\_TLS\_DTPMOD32, [702](#)  
R\_386\_TLS\_DTPOFF32, [702](#)  
R\_386\_TLS\_GD, [702](#)  
R\_386\_TLS\_GD\_32, [702](#)  
R\_386\_TLS\_GD\_CALL, [702](#)  
R\_386\_TLS\_GD\_POP, [702](#)  
R\_386\_TLS\_GD\_PUSH, [702](#)  
R\_386\_TLS\_GOTIE, [702](#)  
R\_386\_TLS\_IE, [702](#)  
R\_386\_TLS\_IE\_32, [702](#)  
R\_386\_TLS\_LDM, [702](#)  
R\_386\_TLS\_LDM\_32, [702](#)  
R\_386\_TLS\_LDM\_CALL, [702](#)  
R\_386\_TLS\_LDM\_POP, [702](#)  
R\_386\_TLS\_LDM\_PUSH, [702](#)  
R\_386\_TLS\_LDO\_32, [702](#)  
R\_386\_TLS\_LE, [702](#)  
R\_386\_TLS\_LE\_32, [702](#)  
R\_386\_TLS\_TPOFF, [702](#)  
R\_386\_TLS\_TPOFF32, [702](#)  
R\_AARCH64\_NONE, [703](#)  
R\_ARM\_ABS12, [703](#)

- R\_ARM\_ABS16, [703](#)
- R\_ARM\_ABS32, [703](#)
- R\_ARM\_ABS8, [703](#)
- R\_ARM\_COPY, [703](#)
- R\_ARM\_GLOB\_DAT, [703](#)
- R\_ARM\_GOT32, [703](#)
- R\_ARM\_GOTOFF, [703](#)
- R\_ARM\_GOTPC, [703](#)
- R\_ARM\_JUMP\_SLOT, [703](#)
- R\_ARM\_NONE, [703](#)
- R\_ARM\_NUM, [703](#)
- R\_ARM\_PC24, [703](#)
- R\_ARM\_PLT32, [703](#)
- R\_ARM\_REL32, [703](#)
- R\_ARM\_RELATIVE, [703](#)
- R\_ARM\_THM\_PC11, [703](#)
- R\_ARM\_THM\_PC9, [703](#)
- R\_X86\_64\_16, [704](#)
- R\_X86\_64\_32, [704](#)
- R\_X86\_64\_32S, [704](#)
- R\_X86\_64\_64, [704](#)
- R\_X86\_64\_8, [704](#)
- R\_X86\_64\_COPY, [704](#)
- R\_X86\_64\_DTPMOD64, [704](#)
- R\_X86\_64\_DTPOFF32, [704](#)
- R\_X86\_64\_DTPOFF64, [704](#)
- R\_X86\_64\_GLOB\_DAT, [704](#)
- R\_X86\_64\_GOT32, [704](#)
- R\_X86\_64\_GOTPCREL, [704](#)
- R\_X86\_64\_GOTTPOFF, [704](#)
- R\_X86\_64\_JUMP\_SLOT, [704](#)
- R\_X86\_64\_NONE, [704](#)
- R\_X86\_64\_PC16, [704](#)
- R\_X86\_64\_PC32, [704](#)
- R\_X86\_64\_PC8, [704](#)
- R\_X86\_64\_PLT32, [704](#)
- R\_X86\_64\_RELATIVE, [704](#)
- R\_X86\_64\_TLSD, [704](#)
- R\_X86\_64\_TLSD, [704](#)
- R\_X86\_64\_TPOFF32, [704](#)
- R\_X86\_64\_TPOFF64, [704](#)
- SHF\_ALLOC, [705](#)
- SHF\_ARM\_COMDEF, [705](#)
- SHF\_ARM\_ENTRYSECT, [704](#)
- SHF\_EXECINSTR, [705](#)
- SHF\_GROUP, [705](#)
- SHF\_INFO\_LINK, [705](#)
- SHF\_LINK\_ORDER, [705](#)
- SHF\_MASKOS, [705](#)
- SHF\_MASKPROC, [705](#)
- SHF\_MERGE, [705](#)
- SHF\_OS\_NONCONFORMING, [705](#)
- SHF\_STRINGS, [705](#)
- SHF\_TLS, [705](#)
- SHF\_WRITE, [705](#)
- SHN\_ABS, [705](#)
- SHN\_COMMON, [705](#)
- SHN\_HIPROC, [705](#)
- SHN\_HIRESERVE, [705](#)
- SHN\_LOPROC, [705](#)
- SHN\_LORESERVE, [705](#)
- SHN\_UNDEF, [705](#)
- SHT\_DYNAMIC, [706](#)
- SHT\_DYNSYM, [706](#)
- SHT\_FINI\_ARRAY, [706](#)
- SHT\_GROUP, [706](#)
- SHT\_HASH, [706](#)
- SHT\_HIOS, [706](#)
- SHT\_HIPROC, [706](#)
- SHT\_HIUSER, [706](#)
- SHT\_INIT\_ARRAY, [706](#)
- SHT\_LOOS, [706](#)
- SHT\_LOPROC, [706](#)
- SHT\_LOUSER, [706](#)
- SHT\_NOBITS, [706](#)
- SHT\_NOTE, [706](#)
- SHT\_NULL, [706](#)
- SHT\_NUM, [706](#)
- SHT\_PREINIT\_ARRAY, [706](#)
- SHT\_PROGBITS, [706](#)
- SHT\_REL, [706](#)
- SHT\_RELA, [706](#)
- SHT\_SHLIB, [706](#)
- SHT\_STRTAB, [706](#)
- SHT\_SYMTAB, [706](#)
- SHT\_SYMTAB\_SHNDX, [706](#)
- STB\_GLOBAL, [707](#)
- STB\_HIOS, [707](#)
- STB\_HIPROC, [707](#)
- STB\_LOCAL, [707](#)
- STB\_LOOS, [707](#)
- STB\_LOPROC, [707](#)
- STB\_WEAK, [707](#)
- STT\_FILE, [707](#)
- STT\_FUNC, [707](#)
- STT\_HIOS, [707](#)
- STT\_HIPROC, [707](#)
- STT\_LOOS, [707](#)
- STT\_LOPROC, [707](#)
- STT\_NOTYPE, [707](#)
- STT\_OBJECT, [707](#)
- STT\_SECTION, [707](#)
- Elf32\_Auxv, [964](#)
  - atype, [965](#)
- Elf32\_Dyn, [965](#)
  - d\_tag, [966](#)
- Elf32\_Ehdr, [966](#)
  - e\_flags, [967](#)
  - e\_machine, [967](#)
  - e\_type, [968](#)
  - e\_version, [968](#)
- Elf32\_Phdr, [969](#)
  - p\_flags, [970](#)
  - p\_type, [970](#)
- ELF32\_R\_TYPE
  - ELF binary format, [689](#)

- Elf32\_Rel, [970](#)
- Elf32\_Rela, [971](#)
- Elf32\_Shdr, [972](#)
  - sh\_flags, [973](#)
  - sh\_type, [973](#)
- ELF32\_ST\_BIND
  - ELF binary format, [689](#)
- ELF32\_ST\_TYPE
  - ELF binary format, [689](#)
- Elf32\_Sym, [974](#)
- Elf64\_Auxv, [975](#)
  - atype, [975](#)
- Elf64\_Dyn, [976](#)
  - d\_tag, [976](#)
- Elf64\_Ehdr, [977](#)
  - e\_flags, [978](#)
  - e\_machine, [978](#)
  - e\_type, [978](#)
  - e\_version, [979](#)
- Elf64\_Phdr, [979](#)
  - p\_flags, [980](#)
  - p\_type, [980](#)
- ELF64\_R\_TYPE
  - ELF binary format, [689](#)
- Elf64\_Rel, [981](#)
- Elf64\_Rela, [981](#)
- Elf64\_Shdr, [982](#)
  - sh\_flags, [983](#)
  - sh\_type, [983](#)
- ELF64\_ST\_BIND
  - ELF binary format, [690](#)
- ELF64\_ST\_TYPE
  - ELF binary format, [690](#)
- Elf64\_Sym, [984](#)
- Elf\_ARM\_SBs
  - ELF binary format, [691](#)
- Elf\_ATs
  - ELF binary format, [691](#)
- Elf\_CIASSs
  - ELF binary format, [692](#)
- Elf\_DATAs
  - ELF binary format, [692](#)
- Elf\_DF\_1s
  - ELF binary format, [692](#)
- Elf\_DF\_P1s
  - ELF binary format, [693](#)
- Elf\_DFs
  - ELF binary format, [693](#)
- Elf\_DTs
  - ELF binary format, [694](#)
- Elf\_EF\_ARM\_s
  - ELF binary format, [695](#)
- Elf\_EIs
  - ELF binary format, [695](#)
- Elf\_EMs
  - ELF binary format, [696](#)
- Elf\_ETs
  - ELF binary format, [698](#)
- Elf\_EVs
  - ELF binary format, [698](#)
- Elf\_MAGs
  - ELF binary format, [699](#)
- Elf\_NT\_s\_core
  - ELF binary format, [699](#)
- Elf\_NT\_s\_obj
  - ELF binary format, [700](#)
- Elf\_OSABIs
  - ELF binary format, [700](#)
- ELF\_PFs
  - ELF binary format, [700](#)
- Elf\_PT\_s
  - ELF binary format, [701](#)
- Elf\_R\_386\_s
  - ELF binary format, [701](#)
- Elf\_R\_AARCH64\_s
  - ELF binary format, [702](#)
- Elf\_R\_ARM\_s
  - ELF binary format, [703](#)
- Elf\_R\_X86\_64\_s
  - ELF binary format, [703](#)
- Elf\_SHF\_s\_ARM
  - ELF binary format, [704](#)
- Elf\_SHFs
  - ELF binary format, [705](#)
- Elf\_SHNs
  - ELF binary format, [705](#)
- Elf\_SHTs
  - ELF binary format, [705](#)
- Elf\_STBs
  - ELF binary format, [706](#)
- Elf\_STTs
  - ELF binary format, [707](#)
- ELFCLASS32
  - ELF binary format, [692](#)
- ELFCLASS64
  - ELF binary format, [692](#)
- ELFCLASSNONE
  - ELF binary format, [692](#)
- ELFCLASSNUM
  - ELF binary format, [692](#)
- ELFDATA2LSB
  - ELF binary format, [692](#)
- ELFDATA2MSB
  - ELF binary format, [692](#)
- ELFDATANONE
  - ELF binary format, [692](#)
- ELFDATANUM
  - ELF binary format, [692](#)
- ELFMAG0
  - ELF binary format, [699](#)
- ELFMAG1
  - ELF binary format, [699](#)
- ELFMAG2
  - ELF binary format, [699](#)
- ELFMAG3
  - ELF binary format, [699](#)

- ELFOSABI\_AIX
  - ELF binary format, [700](#)
- ELFOSABI\_ARM
  - ELF binary format, [700](#)
- ELFOSABI\_FREEBSD
  - ELF binary format, [700](#)
- ELFOSABI\_HPUX
  - ELF binary format, [700](#)
- ELFOSABI\_IRIX
  - ELF binary format, [700](#)
- ELFOSABI\_LINUX
  - ELF binary format, [700](#)
- ELFOSABI\_MODESTO
  - ELF binary format, [700](#)
- ELFOSABI\_NETBSD
  - ELF binary format, [700](#)
- ELFOSABI\_NONE
  - ELF binary format, [700](#)
- ELFOSABI\_OPENBSD
  - ELF binary format, [700](#)
- ELFOSABI\_SOLARIS
  - ELF binary format, [700](#)
- ELFOSABI\_STANDALONE
  - ELF binary format, [700](#)
- ELFOSABI\_SYSV
  - ELF binary format, [700](#)
- ELFOSABI\_TRU64
  - ELF binary format, [700](#)
- EM\_386
  - ELF binary format, [696](#)
- EM\_68HC05
  - ELF binary format, [697](#)
- EM\_68HC08
  - ELF binary format, [697](#)
- EM\_68HC11
  - ELF binary format, [697](#)
- EM\_68HC12
  - ELF binary format, [697](#)
- EM\_68HC16
  - ELF binary format, [697](#)
- EM\_68K
  - ELF binary format, [696](#)
- EM\_860
  - ELF binary format, [696](#)
- EM\_88K
  - ELF binary format, [696](#)
- EM\_960
  - ELF binary format, [696](#)
- EM\_AARCH64
  - ELF binary format, [698](#)
- EM\_ALPHA
  - ELF binary format, [697](#)
- EM\_ALTERA\_NIOS2
  - ELF binary format, [698](#)
- EM\_ARC
  - ELF binary format, [697](#)
- EM\_ARC\_A5
  - ELF binary format, [698](#)
- EM\_ARM
  - ELF binary format, [697](#)
- EM\_AVR
  - ELF binary format, [697](#)
- EM\_COLDFIRE
  - ELF binary format, [697](#)
- EM\_CRIS
  - ELF binary format, [697](#)
- EM\_D10V
  - ELF binary format, [697](#)
- EM\_D30V
  - ELF binary format, [697](#)
- EM\_FIREPATH
  - ELF binary format, [697](#)
- EM\_FR20
  - ELF binary format, [697](#)
- EM\_FR30
  - ELF binary format, [697](#)
- EM\_FX66
  - ELF binary format, [697](#)
- EM\_H8\_300
  - ELF binary format, [697](#)
- EM\_H8\_300H
  - ELF binary format, [697](#)
- EM\_H8\_500
  - ELF binary format, [697](#)
- EM\_H8S
  - ELF binary format, [697](#)
- EM\_HUANY
  - ELF binary format, [697](#)
- EM\_IA\_64
  - ELF binary format, [697](#)
- EM\_JAVELIN
  - ELF binary format, [697](#)
- EM\_M32
  - ELF binary format, [696](#)
- EM\_M32R
  - ELF binary format, [698](#)
- EM\_MICROBLAZE
  - ELF binary format, [698](#)
- EM\_MIPS
  - ELF binary format, [696](#)
- EM\_MIPS\_RS4\_BE
  - ELF binary format, [696](#)
- EM\_MIPS\_X
  - ELF binary format, [697](#)
- EM\_MMIX
  - ELF binary format, [697](#)
- EM\_MN10200
  - ELF binary format, [698](#)
- EM\_MN10300
  - ELF binary format, [698](#)
- EM\_NONE
  - ELF binary format, [696](#)
- EM\_OPENRISC
  - ELF binary format, [698](#)
- EM\_PARISC
  - ELF binary format, [696](#)

EM\_PDSP  
     ELF binary format, [697](#)  
 EM\_PJ  
     ELF binary format, [698](#)  
 EM\_PPC  
     ELF binary format, [697](#)  
 EM\_PRISM  
     ELF binary format, [697](#)  
 EM\_RCE  
     ELF binary format, [697](#)  
 EM\_RH32  
     ELF binary format, [697](#)  
 EM\_RISCV  
     ELF binary format, [698](#)  
 EM\_SH  
     ELF binary format, [697](#)  
 EM\_SPARC  
     ELF binary format, [696](#)  
 EM\_SPARC32PLUS  
     ELF binary format, [696](#)  
 EM\_SPARC64  
     ELF binary format, [696](#)  
 EM\_SPARCV9  
     ELF binary format, [697](#)  
 EM\_ST19  
     ELF binary format, [697](#)  
 EM\_ST7  
     ELF binary format, [697](#)  
 EM\_ST9PLUS  
     ELF binary format, [697](#)  
 EM\_SVX  
     ELF binary format, [697](#)  
 EM\_TILEGX  
     ELF binary format, [698](#)  
 EM\_TILEPRO  
     ELF binary format, [698](#)  
 EM\_TRICORE  
     ELF binary format, [697](#)  
 EM\_V800  
     ELF binary format, [697](#)  
 EM\_V850  
     ELF binary format, [698](#)  
 EM\_VAX  
     ELF binary format, [697](#)  
 EM\_VPP500  
     ELF binary format, [696](#)  
 EM\_X86\_64  
     ELF binary format, [697](#)  
 EM\_XTENSA  
     ELF binary format, [698](#)  
 EM\_ZSP  
     ELF binary format, [697](#)  
 emerg\_write\_bfm\_t  
     L4virtio::Svr::Console::Features, [2120](#)  
 emplace  
     cxx::Avl\_map< KEY\_TYPE, DATA\_TYPE, COMPARE, ALLOC >, [792](#)  
     cxx::Bits::Base\_avl\_set< ITEM\_TYPE, COMPARE, ALLOC, GET\_KEY >, [858](#)  
 empty  
     L4virtio::Svr::Driver\_mem\_region\_t< DATA >, [2182](#)  
 enable\_notify  
     L4virtio::Svr::Virtqueue, [2262](#)  
 enable\_rx\_irq  
     L4::Uart, [1501](#)  
     L4::Uart\_apb, [1508](#)  
 end  
     cxx::Bits::Base\_avl\_set< ITEM\_TYPE, COMPARE, ALLOC, GET\_KEY >, [859](#)  
     cxx::Bits::Bst< Node, Get\_key, Compare >, [875](#)  
     L4::Kip::Mem\_desc, [1280](#)  
 enqueue\_descriptor  
     L4virtio::Driver::Virtqueue, [2074](#)  
 entry\_ip  
     L4vcpu::Vcpu, [2021](#)  
 entry\_sp  
     L4vcpu::Vcpu, [2021](#)  
 Enum\_bitops, [730](#)  
 Enum\_bitops::Enable< T >, [985](#)  
 Enum\_bitops::Has\_marker< T, Void< decltype(enum\_bitops\_enable(declval< T >()))> >, [989](#)  
 Enum\_bitops::Has\_marker< typename, typename >, [986](#)  
 Enum\_bitops\_impl, [730](#)  
 env  
     L4Re::Env, [1633](#)  
 env.h  
     l4re\_env\_t, [2859](#)  
 erase  
     cxx::Bits::Base\_avl\_set< ITEM\_TYPE, COMPARE, ALLOC, GET\_KEY >, [860](#)  
     cxx::H\_list< T, POLICY >, [895](#)  
 err\_no  
     L4::Runtime\_error, [1351](#)  
 Error  
     L4virtio::Svr::Bad\_descriptor, [2083](#)  
 error  
     l4\_thread\_regs\_t, [1547](#)  
 Error codes, [205](#)  
     L4\_E2BIG, [206](#)  
     L4\_EACCESS, [206](#)  
     L4\_EADDRNOTAVAIL, [206](#)  
     L4\_EAGAIN, [206](#)  
     L4\_EBADPROTO, [206](#)  
     L4\_EBUSY, [206](#)  
     L4\_EEXIST, [206](#)  
     L4\_EFAULT, [206](#)  
     L4\_EINVAL, [206](#)  
     L4\_EIO, [206](#)  
     L4\_EIPC\_HI, [207](#)  
     L4\_EIPC\_LO, [207](#)  
     L4\_EMMSGERRRANGE, [207](#)  
     L4\_EMMSGMISSARG, [207](#)  
     L4\_EMMSGTOOLONG, [207](#)

- L4\_EMSGTOOSHORT, [206](#)
- L4\_ENAMETOOLONG, [206](#)
- L4\_ENODEV, [206](#)
- L4\_ENOENT, [206](#)
- L4\_ENOMEM, [206](#)
- L4\_ENOREPLY, [206](#)
- L4\_ENOSPC, [206](#)
- L4\_ENOSYS, [206](#)
- L4\_ENOTDIR, [206](#)
- L4\_ENXIO, [206](#)
- L4\_EOK, [206](#)
- L4\_EPERM, [206](#)
- L4\_ERANGE, [206](#)
- L4\_ERRNOMAX, [206](#)
- l4\_error\_code\_t, [206](#)
- Error Handling, [241](#)
  - l4\_error, [243](#)
  - L4\_IPC\_ENOT\_EXISTENT, [242](#)
  - l4\_ipc\_error, [244](#)
  - l4\_ipc\_error\_code, [245](#)
  - L4\_IPC\_ERROR\_MASK, [242](#)
  - l4\_ipc\_is\_rcv\_error, [246](#)
  - l4\_ipc\_is\_snd\_error, [246](#)
  - L4\_IPC\_REABORTED, [243](#)
  - L4\_IPC\_RECANCELED, [242](#)
  - L4\_IPC\_REMAPFAILED, [242](#)
  - L4\_IPC\_REMSGCUT, [243](#)
  - L4\_IPC\_RERCVPFTO, [242](#)
  - L4\_IPC\_RESNDPFTO, [242](#)
  - L4\_IPC\_RETIMEOUT, [242](#)
  - L4\_IPC\_SEABORTED, [243](#)
  - L4\_IPC\_SECANCELED, [242](#)
  - L4\_IPC\_SEMAPFAILED, [242](#)
  - L4\_IPC\_SEMSGCUT, [243](#)
  - L4\_IPC\_SERCVPFTO, [243](#)
  - L4\_IPC\_SESNDPFTO, [242](#)
  - L4\_IPC\_SETIMEOUT, [242](#)
  - L4\_IPC\_SND\_ERR\_MASK, [242](#)
  - l4\_ipc\_tcr\_error\_t, [242](#)
- ET\_CORE
  - ELF binary format, [698](#)
- ET\_DYN
  - ELF binary format, [698](#)
- ET\_EXEC
  - ELF binary format, [698](#)
- ET\_HIPROC
  - ELF binary format, [698](#)
- ET\_LOPROC
  - ELF binary format, [698](#)
- ET\_NONE
  - ELF binary format, [698](#)
- ET\_REL
  - ELF binary format, [698](#)
- EV\_CURRENT
  - ELF binary format, [699](#)
- EV\_NONE
  - ELF binary format, [699](#)
- Event API, [584](#)
- Event interface, [529](#)
  - l4re\_event\_get\_axis\_info, [530](#)
  - l4re\_event\_get\_buffer, [530](#)
  - l4re\_event\_get\_num\_streams, [530](#)
  - l4re\_event\_get\_stream\_info, [531](#)
  - l4re\_event\_get\_stream\_info\_for\_id, [531](#)
- Event\_buffer\_t
  - L4Re::Event\_buffer\_t< PAYLOAD >, [1657](#)
- Events
  - L4virtio::Svr::Console::Control\_message, [2096](#)
- ex\_regs
  - L4::Thread, [1408](#), [1409](#)
- exc\_handler
  - L4::Thread::Attr, [1422](#)
- exception
  - L4::Exception, [1053](#)
- Exception registers, [266](#)
  - l4\_utcb\_exc, [266](#)
  - l4\_utcb\_exc\_is\_ex\_regs\_exception, [267](#)
  - l4\_utcb\_exc\_is\_pf, [267](#)
  - l4\_utcb\_exc\_pc, [268](#)
  - l4\_utcb\_exc\_pc\_set, [268](#)
- execute
  - L4Re::Ned::Cmd\_control, [1706](#)
- expired
  - L4::lpc\_svr::Timeout, [1243](#)
- ext\_alloc
  - L4vcpu::Vcpu, [2022](#)
- Extended vCPU support, [721](#)
  - l4vcpu\_ext\_alloc, [722](#)
- extra\_str
  - L4::Runtime\_error, [1351](#)
- F\_above
  - L4Re::Video::View, [1920](#)
- F\_auto\_refresh
  - L4Re::Video::Goos, [1898](#)
- F\_dyn\_allocated
  - L4Re::Video::View, [1920](#)
- F\_dynamic\_buffers
  - L4Re::Video::Goos, [1898](#)
- F\_dynamic\_views
  - L4Re::Video::Goos, [1898](#)
- F\_flags\_mask
  - L4Re::Video::View, [1920](#)
- F\_fully\_dynamic
  - L4Re::Video::View, [1920](#)
- F\_l4re\_video\_goos\_auto\_refresh
  - Video API, [563](#)
- F\_l4re\_video\_goos\_dynamic\_buffers
  - Video API, [563](#)
- F\_l4re\_video\_goos\_dynamic\_views
  - Video API, [563](#)
- F\_l4re\_video\_goos\_pointer
  - Video API, [563](#)
- F\_l4re\_video\_view\_above
  - Video API, [563](#)
- F\_l4re\_video\_view\_dyn\_allocated
  - Video API, [563](#)

- F\_l4re\_video\_view\_flags\_mask
  - Video API, [563](#)
- F\_l4re\_video\_view\_none
  - Video API, [563](#)
- F\_l4re\_video\_view\_set\_background
  - Video API, [563](#)
- F\_l4re\_video\_view\_set\_buffer
  - Video API, [563](#)
- F\_l4re\_video\_view\_set\_buffer\_offset
  - Video API, [563](#)
- F\_l4re\_video\_view\_set\_bytes\_per\_line
  - Video API, [563](#)
- F\_l4re\_video\_view\_set\_flags
  - Video API, [563](#)
- F\_l4re\_video\_view\_set\_pixel
  - Video API, [563](#)
- F\_l4re\_video\_view\_set\_position
  - Video API, [563](#)
- F\_none
  - L4Re::Video::View, [1919](#)
- F\_pointer
  - L4Re::Video::Goos, [1898](#)
- F\_set\_background
  - L4Re::Video::View, [1920](#)
- F\_set\_buffer
  - L4Re::Video::View, [1919](#)
- F\_set\_buffer\_offset
  - L4Re::Video::View, [1919](#)
- F\_set\_bytes\_per\_line
  - L4Re::Video::View, [1919](#)
- F\_set\_flags
  - L4Re::Video::View, [1920](#)
- F\_set\_pixel
  - L4Re::Video::View, [1920](#)
- F\_set\_position
  - L4Re::Video::View, [1920](#)
- faccessat
  - L4Re::Vfs::Directory, [1850](#)
- Factory, [282](#)
  - l4\_factory\_create, [284](#)
  - l4\_factory\_create\_factory, [284](#)
  - l4\_factory\_create\_gate, [285](#)
  - l4\_factory\_create\_irq, [286](#)
  - l4\_factory\_create\_task, [287](#)
  - l4\_factory\_create\_thread, [288](#)
  - l4\_factory\_create\_thread\_group, [289](#)
  - l4\_factory\_create\_vcpu\_context, [290](#)
  - l4\_factory\_create\_vm, [291](#)
- factory
  - L4Re::Env, [1634](#), [1635](#)
- fchmod
  - L4Re::Vfs::Generic\_file, [1868](#)
- fdatasync
  - L4Re::Vfs::Regular\_file, [1880](#)
- feature\_negotiated
  - L4virtio::Driver::Device, [2054](#)
- features
  - l4\_icu\_info\_t, [1533](#)
- Fiasco extensions, [157](#)
  - fiasco\_gdt\_get\_entry\_offset, [159](#)
  - fiasco\_gdt\_set, [159](#)
  - fiasco\_ldt\_set, [160](#)
- fiasco\_amd64\_segment\_info
  - segment.h, [2449](#)
- fiasco\_amd64\_set\_fs
  - segment.h, [2450](#)
- fiasco\_amd64\_set\_segment\_base
  - segment.h, [2451](#)
- fiasco\_dump\_kmem\_stats
  - kdump.h, [3197](#)
- fiasco\_gdt\_get\_entry\_offset
  - Fiasco extensions, [159](#)
- fiasco\_gdt\_set
  - Fiasco extensions, [159](#)
- fiasco\_ldt\_set
  - Fiasco extensions, [160](#)
- fiasco\_tbuf\_log
  - Kernel Tracing, [171](#)
- fiasco\_tbuf\_log\_3val
  - Kernel Tracing, [171](#)
- fiasco\_tbuf\_log\_binary
  - Kernel Tracing, [172](#)
- finalize\_request
  - L4virtio::Svr::Block\_dev\_base< Ds\_data >, [2089](#)
- find
  - cxx::Bits::Bst< Node, Get\_key, Compare >, [876](#)
  - cxx::String, [951](#)
  - L4::Basic\_registry, [998](#)
  - L4Re::Rm, [1729](#)
  - L4virtio::Svr::Driver\_mem\_list\_t< DATA >, [2174](#)
  - Rm, [2327](#)
- find\_next\_used
  - L4virtio::Driver::Virtqueue, [2075](#)
- find\_node
  - cxx::Bits::Base\_avl\_set< ITEM\_TYPE, COMPARE, ALLOC, GET\_KEY >, [860](#)
  - cxx::Bits::Bst< Node, Get\_key, Compare >, [876](#)
- finish
  - L4virtio::Svr::Virtqueue, [2263](#), [2264](#)
- finish\_rx
  - L4virtio::Driver::Virtio\_net\_device, [2064](#)
- first
  - L4::Kip::Mem\_desc, [1280](#)
- first\_free\_cap
  - L4Re::Env, [1635](#)
- first\_free\_utcb
  - L4Re::Env, [1636](#)
- Fixed\_paddr
  - L4Re::Mem\_alloc, [1685](#)
- Flags
  - L4::Type\_info::Demand\_t< CAPS, FLAGS, MEM, PORTS >, [1443](#)
  - L4::Types::Flags< BITS\_ENUM, UNDERLYING >, [1479](#)
  - L4Re::Dataspace::F, [1615](#)
  - L4Re::Video::Goos, [1898](#)



- L4Re::Video::View, [1919](#)
- flags
  - l4\_exc\_regs\_t, [1530](#)
  - l4\_msgtag\_t, [1539](#)
  - L4Re::Dataspace, [1608](#)
  - l4re\_env\_cap\_entry\_t, [1932](#)
  - L4virtio::Svr::Driver\_mem\_region\_t< DATA >, [2183](#)
- Flexpages, [173](#)
  - L4\_CAP\_FPAGE\_D, [177](#)
  - L4\_CAP\_FPAGE\_R, [176](#)
  - L4\_cap\_fpage\_rights, [176](#)
  - L4\_CAP\_FPAGE\_RO, [176](#)
  - L4\_CAP\_FPAGE\_RS, [177](#)
  - L4\_CAP\_FPAGE\_RSD, [177](#)
  - L4\_CAP\_FPAGE\_RW, [177](#)
  - L4\_CAP\_FPAGE\_RWD, [177](#)
  - L4\_CAP\_FPAGE\_RWS, [177](#)
  - L4\_CAP\_FPAGE\_RWSD, [177](#)
  - L4\_CAP\_FPAGE\_S, [176](#)
  - L4\_CAP\_FPAGE\_W, [176](#)
  - l4\_fpage, [179](#)
  - L4\_FPAGE\_ADDR\_BITS, [178](#)
  - L4\_FPAGE\_ADDR\_SHIFT, [178](#)
  - l4\_fpage\_all, [180](#)
  - L4\_fpage\_consts, [177](#)
  - l4\_fpage\_contains, [180](#)
  - L4\_fpage\_control, [178](#)
  - L4\_FPAGE\_CONTROL\_MASK, [178](#)
  - L4\_FPAGE\_CONTROL\_OFFSET\_SHIFT, [178](#)
  - l4\_fpage\_invalid, [181](#)
  - L4\_FPAGE\_IO, [179](#)
  - l4\_fpage\_ioport, [181](#)
  - l4\_fpage\_max\_order, [182](#)
  - l4\_fpage\_memaddr, [183](#)
  - L4\_FPAGE\_MEMORY, [179](#)
  - L4\_FPAGE\_OBJ, [179](#)
  - l4\_fpage\_obj, [183](#)
  - l4\_fpage\_page, [184](#)
  - L4\_fpage\_rights, [178](#)
  - l4\_fpage\_rights, [184](#)
  - L4\_FPAGE\_RIGHTS\_ALL, [178](#)
  - L4\_FPAGE\_RIGHTS\_BITS, [178](#)
  - L4\_FPAGE\_RIGHTS\_MASK, [178](#)
  - L4\_FPAGE\_RIGHTS\_SHIFT, [177](#)
  - L4\_FPAGE\_RO, [178](#)
  - L4\_FPAGE\_RW, [178](#)
  - L4\_FPAGE\_RWX, [179](#)
  - L4\_FPAGE\_RX, [179](#)
  - l4\_fpage\_set\_rights, [185](#)
  - l4\_fpage\_size, [186](#)
  - L4\_FPAGE\_SIZE\_BITS, [178](#)
  - L4\_FPAGE\_SIZE\_SHIFT, [178](#)
  - L4\_FPAGE\_SPECIAL, [179](#)
  - L4\_fpage\_type, [179](#)
  - l4\_fpage\_type, [187](#)
  - L4\_FPAGE\_TYPE\_BITS, [178](#)
  - L4\_FPAGE\_TYPE\_SHIFT, [177](#)
  - L4\_FPAGE\_W, [178](#)
  - L4\_FPAGE\_X, [178](#)
  - l4\_iofpage, [187](#)
  - L4\_IOPORT\_MAX, [176](#)
  - l4\_is\_fpage\_valid, [188](#)
  - l4\_is\_fpage\_writable, [189](#)
  - l4\_obj\_fpage, [190](#)
  - L4\_WHOLE\_ADDRESS\_SPACE, [175](#)
  - L4\_WHOLE\_IOADDRESS\_SPACE, [176](#)
- flush
  - Mac\_table< Size >, [2314](#)
- foreach\_available\_event
  - L4Re::Util::Event\_buffer\_consumer\_t< PAYLOAD >, [1797](#)
- fpage
  - L4::Cap\_base, [1015](#)
- free
  - cxx::Base\_slab< Obj\_size, Slab\_size, Max\_free, Alloc >, [811](#)
  - cxx::Base\_slab\_static< Obj\_size, Slab\_size, Max\_free, Alloc >, [816](#)
  - cxx::List\_alloc, [912](#)
  - cxx::Slab< Type, Slab\_size, Max\_free, Alloc >, [941](#)
  - L4Re::Cap\_alloc, [1593](#)
  - L4Re::Util::\_Cap\_alloc, [1750](#)
  - L4Re::Util::Counting\_cap\_alloc< COUNTER-TYPE, Dbg >, [1785](#)
- free\_area
  - L4Re::Rm, [1730](#)
  - Rm, [2328](#)
- free\_capability
  - L4Re::Util::Names::Name\_space, [1814](#)
- free\_descriptor
  - L4virtio::Driver::Virtqueue, [2075](#)
- free\_dynamic\_entry
  - L4Re::Util::Names::Name\_space, [1815](#)
- free\_epiface
  - L4Re::Util::Names::Name\_space, [1815](#)
- free\_fd
  - L4Re::Vfs::Fs, [1862](#)
- free\_marker
  - l4\_thread\_regs\_t, [1547](#)
- free\_objects
  - cxx::Base\_slab< Obj\_size, Slab\_size, Max\_free, Alloc >, [811](#)
  - cxx::Base\_slab\_static< Obj\_size, Slab\_size, Max\_free, Alloc >, [817](#)
- from\_ci
  - L4::lpc::Cap< T >, [1113](#)
- from\_dec
  - cxx::String, [952](#)
- From\_device
  - L4Re::Dma\_space, [1625](#)
- from\_hex
  - cxx::String, [953](#)
- from\_raw

- L4::Types::Flags< BITS\_ENUM, UNDERLYING >, 1480
- fstat
  - L4Re::Vfs::Be\_file, 1843
  - L4Re::Vfs::Generic\_file, 1868
- fsync
  - L4Re::Vfs::Regular\_file, 1880
- ftruncate
  - L4Re::Vfs::Regular\_file, 1881
- full
  - L4virtio::Svr::Driver\_mem\_list\_t< DATA >, 2175
- g
  - L4Re::Video::Pixel\_info, 1915
- gcd
  - cxx, 726
- generic\_write
  - L4::Uart, 1502
- get
  - cxx::Bitfield< T, LSB, MSB >, 821
  - cxx::Ref\_ptr< T, CNT >, 933
  - L4::lpc::Iostream, 1122, 1123
  - L4::lpc::Istream, 1131, 1132
  - L4Re::Core::Ref\_ptr< T, CNT >, 1601
  - L4Re::Env, 1636
  - L4Re::Rm::Unique\_region< T >, 1744
  - L4Re::Video::Color\_component, 1892
  - L4vbus::Gpio\_module, 1969
  - L4vbus::Gpio\_pin, 1979
  - L4virtio::Ptr< T >, 2081
  - Rm::Unique\_region< T >, 2339
- get\_areas
  - L4Re::Rm, 1731
  - Rm, 2329
- get\_attr
  - L4::Vcon, 1518
- get\_avail\_idx
  - L4virtio::Virtqueue, 2277
- get\_axis\_info
  - L4Re::Event, 1648
- get\_buffer
  - L4Re::Event, 1649
- get\_buffer\_demand
  - L4::Epiface, 1043
  - L4::Server\_object\_t< IFACE, BASE >, 1381
- get\_cap
  - L4Re::Env, 1637, 1638
- get\_char
  - L4::Uart, 1502
  - L4::Uart\_apb, 1508
- get\_cmd
  - L4virtio::Svr::Dev\_config, 2152
- get\_epiface
  - L4Re::Util::Names::Name\_space, 1816
- get\_fb
  - L4Re::Util::Video::Goos\_svr, 1838
- get\_file
  - L4Re::Vfs::Fs, 1862
- get\_info
  - L4Re::Rm, 1732
  - Rm, 2329
- get\_infos
  - L4::lpc\_gate, 1211
- get\_lock
  - L4Re::Vfs::Regular\_file, 1882
- get\_num\_streams
  - L4Re::Event, 1650
- get\_object\_name
  - L4::Debugger, 1028
- get\_random
  - L4Re::Random, 1715
- get\_rcv\_cap
  - L4::lpc\_svr::Server\_iface, 1236
  - L4Re::Util::Br\_manager, 1770
- get\_regions
  - L4Re::Rm, 1733
  - Rm, 2330
- get\_request
  - L4virtio::Svr::Virtio\_gpio< Request\_handler, Epiface >::Request\_processor, 2221
  - L4virtio::Svr::Virtio\_i2c< Request\_handler, Epiface >::Request\_processor, 2232
  - L4virtio::Svr::Virtio\_spi< Spi\_request\_handler, Epiface >::Request\_processor, 2254
  - Virtio\_net\_request, 2352
- get\_resource
  - L4vbus::Device, 1962
- get\_static\_buffer
  - L4Re::Video::Goos, 1902
- get\_status\_flags
  - L4Re::Vfs::Generic\_file, 1869
- get\_stream\_info
  - L4Re::Event, 1651
- get\_stream\_info\_for\_id
  - L4Re::Event, 1652
- get\_stream\_state\_for\_id
  - L4Re::Event, 1653
- get\_tail\_avail\_idx
  - L4virtio::Virtqueue, 2278
- get\_unshifted
  - cxx::Bitfield< T, LSB, MSB >, 821
- get\_value
  - L4::lpc::Varg, 1196
- get\_writeback
  - L4virtio::Svr::Block\_dev\_base< Ds\_data >, 2090
- getitimer
  - L4Re::Itas, 1668
- global\_id
  - L4::Debugger, 1029
- gran\_offset
  - l4\_sched\_cpu\_set\_t, 1543
- Grant
  - L4::lpc::Snd\_fpage, 1187
- granularity
  - l4\_sched\_cpu\_set\_t, 1541
- guest\_features
  - L4virtio::Svr::Dev\_config, 2153

- H\_list\_item\_t
  - cxx::H\_list\_item\_t< ELEM\_TYPE >, [901](#)
- handle\_control\_message
  - L4virtio::Svr::Console::Virtio\_con, [2132](#)
- handle\_expired\_timeouts
  - L4::lpc\_svr::Timeout\_queue, [1245](#)
- handle\_l4virtio\_port\_tx
  - Virtio\_switch, [2356](#)
- handle\_mem\_cmd\_write
  - L4virtio::Svr::Device\_t< DATA >, [2169](#)
- has\_alpha
  - L4Re::Video::Pixel\_info, [1915](#)
- has\_error
  - l4\_msgtag\_t, [1539](#)
- has\_more
  - L4virtio::Svr::Request\_processor, [2187](#)
- hdr
  - L4virtio::Svr::Dev\_config, [2153](#)
- i
  - L4vcpu::Vcpu, [2022](#), [2023](#)
- IA32 Port I/O API, [645](#)
- l4util\_in16, [646](#)
- l4util\_in32, [646](#)
- l4util\_in8, [646](#)
- l4util\_ins16, [647](#)
- l4util\_ins32, [647](#)
- l4util\_ins8, [648](#)
- l4util\_ioport\_map, [648](#)
- l4util\_out16, [649](#)
- l4util\_out32, [649](#)
- l4util\_out8, [650](#)
- l4util\_outs16, [650](#)
- l4util\_outs32, [650](#)
- l4util\_outs8, [651](#)
- id
  - L4::Kobject\_typeid< T >, [1300](#)
  - L4::Kobject\_typeid< void >, [1304](#)
- id\_received
  - L4::lpc::Snd\_fpage, [1189](#)
- idle\_time
  - L4::Scheduler, [1357](#)
- Ignore\_sigaction
  - L4Re::ltas, [1668](#)
- In\_area
  - L4Re::Rm::F, [1738](#)
  - Rm::F, [2334](#)
- inc
  - L4Re::Util::Counter< COUNTER >, [1779](#)
  - L4Re::Util::Counter\_atomic< COUNTER >, [1781](#)
- include.mk - Header File Role, [38](#)
- indirect\_bfm\_t
  - L4virtio::Virtqueue::Desc::Flags, [2292](#)
- Info
  - L4::Kip::Mem\_desc, [1276](#)
- info
  - L4::lcu, [1080](#)
  - L4::Scheduler, [1357](#)
  - L4Re::Dataspace, [1609](#)
  - L4Re::Mem\_alloc, [1686](#)
  - L4Re::Video::Goos, [1903](#)
  - L4Re::Video::View, [1920](#)
- Info\_acpi\_rsdp
  - L4::Kip::Mem\_desc, [1276](#)
- Info\_sub\_type
  - L4::Kip::Mem\_desc, [1276](#)
- inhibitor.h
  - l4re\_inhibitor\_acquire, [2820](#)
  - l4re\_inhibitor\_next\_lock\_info, [2821](#)
  - l4re\_inhibitor\_release, [2821](#)
- init
  - L4Re::Util::Event\_t< PAYLOAD >, [1806](#)
  - L4virtio::Svr::Driver\_mem\_list\_t< DATA >, [2176](#)
- init\_infos
  - L4Re::Util::Video::Goos\_svr, [1838](#)
- init\_mem\_info
  - L4virtio::Svr::Device\_t< DATA >, [2170](#)
- init\_poll
  - L4Re::Util::Event\_t< PAYLOAD >, [1807](#)
- init\_queue
  - L4virtio::Driver::Virtqueue, [2076](#)
- Initial Environment, [569](#)
- l4re\_env, [570](#)
- l4re\_env\_get\_cap, [571](#)
- l4re\_env\_get\_cap\_e, [571](#)
- l4re\_env\_get\_cap\_l, [572](#)
- l4re\_kip, [573](#)
- Initial Environment and Application Bootstrapping, [25](#)
- Initial Memory Allocator and Factory, [28](#)
- initial\_caps
  - L4Re::Env, [1639](#)
- initialize\_rings
  - L4virtio::Driver::Virtqueue, [2077](#)
- insert
  - cxx::Avl\_map< KEY\_TYPE, DATA\_TYPE, COMPARE, ALLOC >, [792](#)
  - cxx::Avl\_tree< Node, Get\_key, Compare >, [804](#)
  - cxx::Bits::Base\_avl\_set< ITEM\_TYPE, COMPARE, ALLOC, GET\_KEY >, [860](#)
  - cxx::H\_list< T, POLICY >, [895](#)
- insert\_after
  - cxx::H\_list< T, POLICY >, [896](#)
- insert\_before
  - cxx::H\_list< T, POLICY >, [896](#)
- Integer Types, [444](#)
- interface
  - L4::Meta, [1313](#)
- Interface Definition Language, [30](#)
- Interface for asynchronous ISR handlers with a given IRQ capability., [469](#)
- l4irq\_request\_cap, [470](#)
- Interface for asynchronous ISR handlers., [467](#)
- l4irq\_release, [468](#)
- l4irq\_request, [468](#)
- Interface using direct functionality., [460](#), [465](#)
- l4irq\_attach, [461](#)
- l4irq\_attach\_cap, [465](#)

- l4irq\_attach\_cap\_ft, [465](#)
- l4irq\_attach\_ft, [461](#)
- l4irq\_attach\_thread, [461](#)
- l4irq\_attach\_thread\_cap, [466](#)
- l4irq\_attach\_thread\_cap\_ft, [466](#)
- l4irq\_attach\_thread\_ft, [462](#)
- l4irq\_detach, [462](#)
- l4irq\_unmask, [463](#)
- l4irq\_unmask\_and\_wait\_any, [463](#)
- l4irq\_wait, [464](#)
- l4irq\_wait\_any, [464](#)
- Internal, [594](#)
  - L4SHMC\_RINGBUF\_DATA, [595](#)
  - L4SHMC\_RINGBUF\_DATA\_SIZE, [595](#)
  - L4SHMC\_RINGBUF\_HEAD, [596](#)
- Internal constants, [628](#)
- Internal functions, [676](#)
- Internal Helpers, [192](#)
- internal\_loop
  - L4::Server< LOOP\_HOOKS >, [1370](#)
- Interrupt controller, [314](#)
  - l4\_icu\_bind, [317](#)
  - l4\_icu\_bind\_u, [318](#)
  - L4\_ICU\_FLAG\_MSI, [317](#)
  - L4\_icu\_flags, [317](#)
  - l4\_icu\_info, [319](#)
  - l4\_icu\_info\_t, [316](#)
  - l4\_icu\_info\_u, [320](#)
  - l4\_icu\_mask, [321](#)
  - l4\_icu\_mask\_u, [322](#)
  - l4\_icu\_msi\_info, [323](#)
  - l4\_icu\_msi\_info\_u, [324](#)
  - l4\_icu\_set\_mode, [325](#)
  - l4\_icu\_set\_mode\_u, [326](#)
  - l4\_icu\_unbind, [327](#)
  - l4\_icu\_unbind\_u, [328](#)
  - l4\_icu\_unmask, [329](#)
  - l4\_icu\_unmask\_u, [330](#)
- Introduction, [3](#)
- Invalid
  - L4::Cap\_base, [1011](#)
  - L4virtio::Ptr< T >, [2080](#)
- Invalid\_capability
  - L4::Invalid\_capability, [1089](#)
- Invalid\_type
  - L4virtio::Ptr< T >, [2080](#)
- Io
  - L4::lpc::Gen\_fpage, [1116](#)
- io
  - L4::lpc::Rcv\_fpage, [1176](#)
  - L4::lpc::Snd\_fpage, [1189](#)
- IO interface, [450](#)
  - L4IO\_DEVICE\_ANY, [452](#)
  - L4IO\_DEVICE\_INVALID, [452](#)
  - L4IO\_DEVICE\_OTHER, [452](#)
  - L4IO\_DEVICE\_PCI, [452](#)
  - l4io\_device\_types\_t, [451](#)
  - L4IO\_DEVICE\_USB, [452](#)
  - l4io\_has\_resource, [453](#)
  - l4io\_iomem\_flags\_t, [452](#)
  - l4io\_lookup\_device, [453](#)
  - l4io\_lookup\_resource, [453](#)
  - L4IO\_MEM\_CACHED, [452](#)
  - L4IO\_MEM\_EAGER\_MAP, [452](#)
  - L4IO\_MEM\_NONCACHED, [452](#)
  - L4IO\_MEM\_USE\_MTRR, [452](#)
  - L4IO\_MEM\_USE\_RESERVED\_AREA, [452](#)
  - l4io\_release\_iomem, [454](#)
  - l4io\_release\_ioport, [454](#)
  - l4io\_request\_iomem, [455](#)
  - l4io\_request\_iomem\_region, [456](#)
  - l4io\_request\_ioport, [456](#)
  - l4io\_request\_resource\_iomem, [457](#)
  - L4IO\_RESOURCE\_ANY, [452](#)
  - L4IO\_RESOURCE\_INVALID, [452](#)
  - L4IO\_RESOURCE\_IRQ, [452](#)
  - L4IO\_RESOURCE\_MEM, [452](#)
  - L4IO\_RESOURCE\_PORT, [452](#)
  - l4io\_resource\_t, [451](#)
  - l4io\_resource\_types\_t, [452](#)
- Io, the Io Server, [61](#)
- io.h
  - l4io\_get\_root\_device, [2556](#)
  - l4io\_iterate\_devices, [2556](#)
  - l4io\_request\_all\_ioports, [2556](#)
  - l4io\_request\_icu, [2557](#)
- io\_page\_fault
  - L4::io\_pager, [1093](#)
- ioctl
  - L4Re::Vfs::Special\_file, [1889](#)
- loststream
  - L4::lpc::loststream, [1121](#)
- IPC Helpers, [458](#)
  - throw\_ipc\_exception, [458](#)
- IPC-Gate API, [275](#)
  - l4\_ipc\_gate\_get\_infos, [276](#)
  - l4\_rcv\_ep\_bind\_snd\_destination, [277](#)
  - l4\_rcv\_ep\_bind\_thread, [278](#)
- ipc.h
  - l4\_ipc\_to\_errno, [3165](#)
- ipc\_client
  - L4\_RPC\_DEF, [3078](#)
- ipc\_iface
  - L4\_INLINE\_RPC, [3086](#)
  - L4\_INLINE\_RPC\_NF, [3086](#)
  - L4\_INLINE\_RPC\_NF\_OP, [3086](#)
  - L4\_INLINE\_RPC\_OP, [3087](#)
  - L4\_RPC, [3087](#)
  - L4\_RPC\_NF, [3088](#)
  - L4\_RPC\_NF\_OP, [3088](#)
  - L4\_RPC\_OP, [3089](#)
- ipc\_stream
  - operator<<, [2619–2621](#)
  - operator>>, [2621–2625](#)
- irq
  - L4Re::Util::Event\_t< PAYLOAD >, [1807](#)

- IRQ handling library, [459](#)
- irq\_disable\_save
  - L4vcpu::Vcpu, [2023](#)
- irq\_enable
  - L4vbus::Pci\_dev, [1991](#)
  - L4vbus::Pci\_host\_bridge, [1997](#)
  - L4vcpu::Vcpu, [2023](#)
- irq\_restore
  - L4vcpu::Vcpu, [2024](#)
- IRQs, [331](#)
  - I4\_irq\_bind\_vcpu, [333](#)
  - I4\_irq\_bind\_vcpu\_u, [334](#)
  - I4\_irq\_detach, [336](#)
  - I4\_irq\_detach\_u, [337](#)
  - L4\_IRQ\_F\_BOTH, [333](#)
  - L4\_IRQ\_F\_BOTH\_EDGE, [333](#)
  - L4\_IRQ\_F\_CLEAR\_WAKEUP, [333](#)
  - L4\_IRQ\_F\_EDGE, [333](#)
  - L4\_IRQ\_F\_LEVEL, [333](#)
  - L4\_IRQ\_F\_LEVEL\_HIGH, [333](#)
  - L4\_IRQ\_F\_LEVEL\_LOW, [333](#)
  - L4\_IRQ\_F\_MASK, [333](#)
  - L4\_IRQ\_F\_NEG, [333](#)
  - L4\_IRQ\_F\_NEG\_EDGE, [333](#)
  - L4\_IRQ\_F\_NONE, [333](#)
  - L4\_IRQ\_F\_POS, [333](#)
  - L4\_IRQ\_F\_POS\_EDGE, [333](#)
  - L4\_IRQ\_F\_SET\_MODE, [333](#)
  - L4\_IRQ\_F\_SET\_WAKEUP, [333](#)
  - L4\_irq\_mode, [333](#)
  - I4\_irq\_receive, [338](#)
  - I4\_irq\_receive\_u, [339](#)
  - I4\_irq\_trigger, [340](#)
  - I4\_irq\_trigger\_u, [341](#)
  - I4\_irq\_unmask, [342](#)
  - I4\_irq\_unmask\_u, [343](#)
  - I4\_irq\_wait, [344](#)
  - I4\_irq\_wait\_u, [345](#)
- is\_compatible
  - L4vbus::Device, [1963](#)
- is\_compound
  - L4::lpc::Snd\_fpage, [1190](#)
- is\_irq\_entry
  - L4vcpu::Vcpu, [2025](#)
- is\_nil
  - L4::lpc::Varg, [1196](#)
- is\_of
  - L4::lpc::Varg, [1197](#)
- is\_of\_int
  - L4::lpc::Varg, [1198](#)
- is\_online
  - L4::Scheduler, [1358](#)
- is\_page\_fault\_entry
  - L4vcpu::Vcpu, [2025](#)
- is\_static
  - L4Re::Util::Dataspace\_svr, [1791](#)
- is\_valid
  - L4::Cap\_base, [1016](#)
  - L4Re::Rm::Unique\_region< T >, [1744](#)
  - L4virtio::Ptr< T >, [2081](#)
  - Rm::Unique\_region< T >, [2339](#)
- is\_virtual
  - L4::Kip::Mem\_desc, [1281](#)
- is\_writable
  - L4virtio::Svr::Driver\_mem\_region\_t< DATA >, [2183](#)
- Istream
  - L4::lpc::Istream, [1130](#)
- itas
  - L4Re::Env, [1640](#)
- Item\_bytes
  - L4::lpc::Msg, [752](#)
- Item\_words
  - L4::lpc::Msg, [752](#)
- iter
  - cxx::Bits::Basic\_list< POLICY >, [868](#)
  - cxx::H\_list< T, POLICY >, [897](#)
- Iterator
  - cxx::Avl\_tree< Node, Get\_key, Compare >, [804](#)
- kdebug.h
  - \_\_I4\_kdebug\_3\_text, [3181](#)
  - \_\_I4\_kdebug\_op, [3182](#)
  - \_\_I4\_kdebug\_op\_1, [3183](#)
  - \_\_I4\_kdebug\_text, [3185](#)
  - I4\_kd\_enter, [3186](#)
  - I4\_kd\_outchar, [3187](#)
  - I4\_kd\_outdec, [3188](#)
  - I4\_kd\_outhex12, [3188](#)
  - I4\_kd\_outhex16, [3189](#)
  - I4\_kd\_outhex20, [3189](#)
  - I4\_kd\_outhex32, [3190](#)
  - I4\_kd\_outhex64, [3190](#)
  - I4\_kd\_outhex8, [3191](#)
  - I4\_kd\_outnstring, [3192](#)
  - I4\_kd\_outstring, [3193](#)
  - I4\_kd\_outumword, [3193](#)
  - I4\_kdebug\_ops\_t, [3181](#)
- kdump.h
  - fiasco\_dump\_kmem\_stats, [3197](#)
- Kept\_ds
  - L4Re::Rm, [1722](#)
  - Rm, [2323](#)
- Kernel
  - L4Re::Rm::F, [1739](#)
  - Rm::F, [2334](#)
- Kernel ABI, [16](#)
- Kernel Debugger, [161](#)
  - I4\_debugger\_add\_image\_info, [162](#)
  - I4\_debugger\_get\_object\_name, [163](#)
  - I4\_debugger\_global\_id, [164](#)
  - I4\_debugger\_kobj\_to\_id, [164](#)
  - I4\_debugger\_query\_log\_name, [165](#)
  - I4\_debugger\_query\_log\_typeid, [166](#)
  - I4\_debugger\_query\_object\_name, [167](#)
  - I4\_debugger\_set\_object\_name, [168](#)
  - I4\_debugger\_switch\_log, [168](#)

- Kernel Factory, [46](#)
- Kernel Information Dump, [169](#)
- Kernel Interface Page, [425](#)
  - [l4\\_kernel\\_info\\_t](#), [427](#)
  - [l4\\_kernel\\_info\\_version\\_offset](#), [428](#)
  - [l4\\_kip](#), [428](#)
  - [l4\\_kip\\_clock](#), [428](#)
  - [l4\\_kip\\_clock\\_lw](#), [429](#)
  - [l4\\_kip\\_clock\\_ns](#), [430](#)
  - [L4\\_KIP\\_OFFS\\_READ\\_NS](#), [427](#)
  - [L4\\_KIP\\_OFFS\\_READ\\_US](#), [427](#)
  - [l4\\_kip\\_version](#), [430](#)
  - [l4\\_kip\\_version\\_string](#), [431](#)
- Kernel Interface Page API, [708](#)
  - [l4util\\_kip\\_for\\_each\\_feature](#), [708](#)
  - [l4util\\_kip\\_kernel\\_abi\\_version](#), [709](#)
  - [l4util\\_kip\\_kernel\\_has\\_feature](#), [709](#)
- Kernel Objects, [273](#)
- Kernel Tracing, [170](#)
  - [fiasco\\_tbuf\\_log](#), [171](#)
  - [fiasco\\_tbuf\\_log\\_3val](#), [171](#)
  - [fiasco\\_tbuf\\_log\\_binary](#), [172](#)
- Kernel-provided semaphore, [360](#)
  - [l4\\_semaphore\\_down](#), [361](#)
  - [l4\\_semaphore\\_up](#), [361](#)
- kip.h
  - [l4\\_kip\\_for\\_each\\_feature](#), [3345](#)
  - [l4\\_kip\\_kernel\\_has\\_feature](#), [3345](#)
- kobj\_to\_id
  - [L4::Debugger](#), [1030](#)
- kobject\_typeid
  - [L4 kernel object type information](#), [281](#)
- Kumem allocator utility, [560](#)
- Kumem utilities, [579](#)
  - [kumem\\_alloc](#), [580](#)
- kumem\_alloc
  - [Kumem utilities](#), [580](#)
- kumem\_alloc.h
  - [l4re\\_util\\_kumem\\_alloc](#), [2836](#)
- L
  - [cxx::Bits::Direction](#), [885](#)
- L4, [731](#)
  - [cap\\_cast](#), [736](#), [737](#)
  - [cap\\_dynamic\\_cast](#), [738](#)
  - [cap\\_reinterpret\\_cast](#), [739](#), [740](#)
  - [PROTO\\_ANY](#), [735](#)
  - [PROTO\\_EMPTY](#), [735](#)
  - [round\\_order](#), [740](#)
  - [trunc\\_order](#), [741](#)
- L4 IPC Opcodes, [470](#)
  - [L4\\_ICU\\_OP\\_BIND](#), [472](#)
  - [L4\\_ICU\\_OP\\_INFO](#), [472](#)
  - [L4\\_ICU\\_OP\\_MASK](#), [472](#)
  - [L4\\_ICU\\_OP\\_MSI\\_INFO](#), [472](#)
  - [L4\\_ICU\\_OP\\_SET\\_MODE](#), [472](#)
  - [L4\\_ICU\\_OP\\_UNBIND](#), [472](#)
  - [L4\\_ICU\\_OP\\_UNMASK](#), [472](#)
  - [L4\\_icu\\_opcode](#), [471](#)
  - [L4\\_IPC\\_GATE\\_BIND\\_OP](#), [472](#)
  - [L4\\_IPC\\_GATE\\_GET\\_INFO\\_OP](#), [472](#)
  - [L4\\_ipc\\_gate\\_ops](#), [472](#)
  - [L4\\_PLATFORM\\_CTL\\_CPU\\_ALLOW\\_SHUTDOWN\\_OP](#), [473](#)
  - [L4\\_PLATFORM\\_CTL\\_CPU\\_DISABLE\\_OP](#), [473](#)
  - [L4\\_PLATFORM\\_CTL\\_CPU\\_ENABLE\\_OP](#), [473](#)
  - [L4\\_platform\\_ctl\\_ops](#), [472](#)
  - [L4\\_PLATFORM\\_CTL\\_SET\\_TASK\\_ASID\\_OP](#), [473](#)
  - [L4\\_PLATFORM\\_CTL\\_SYS\\_SHUTDOWN\\_OP](#), [473](#)
  - [L4\\_PLATFORM\\_CTL\\_SYS\\_SUSPEND\\_OP](#), [473](#)
  - [L4\\_TASK\\_ADD\\_KU\\_MEM\\_OP](#), [473](#)
  - [L4\\_TASK\\_CAP\\_INFO\\_OP](#), [473](#)
  - [L4\\_TASK\\_LDT\\_SET\\_X86\\_OP](#), [473](#)
  - [L4\\_TASK\\_MAP\\_OP](#), [473](#)
  - [L4\\_TASK\\_MAP\\_VGICC\\_ARM\\_OP](#), [473](#)
  - [L4\\_task\\_ops](#), [473](#)
  - [L4\\_TASK\\_UNMAP\\_OP](#), [473](#)
  - [L4\\_THREAD\\_AMD64\\_GET\\_SEGMENT\\_INFO\\_OP](#), [474](#)
  - [L4\\_THREAD\\_AMD64\\_SET\\_SEGMENT\\_BASE\\_OP](#), [474](#)
  - [L4\\_THREAD\\_ARM\\_TPIDRURO\\_OP](#), [474](#)
  - [L4\\_THREAD\\_CONTROL\\_OP](#), [473](#)
  - [L4\\_THREAD\\_EX\\_REGS\\_OP](#), [474](#)
  - [L4\\_THREAD\\_MODIFY\\_SENDER\\_OP](#), [474](#)
  - [L4\\_THREAD\\_OPCODE\\_MASK](#), [474](#)
  - [L4\\_thread\\_ops](#), [473](#)
  - [L4\\_THREAD\\_REGISTER\\_DELETE\\_IRQ\\_OP](#), [474](#)
  - [L4\\_THREAD\\_REGISTER\\_DOORBELL\\_IRQ\\_OP](#), [474](#)
  - [L4\\_THREAD\\_STATS\\_OP](#), [474](#)
  - [L4\\_THREAD\\_SWITCH\\_OP](#), [474](#)
  - [L4\\_THREAD\\_VCPU\\_CONTROL\\_OP](#), [474](#)
  - [L4\\_THREAD\\_VCPU\\_RESUME\\_OP](#), [474](#)
  - [L4\\_THREAD\\_X86\\_GDT\\_OP](#), [474](#)
  - [L4\\_VCON\\_GET\\_ATTR\\_OP](#), [474](#)
  - [L4\\_vcon\\_ops](#), [474](#)
  - [L4\\_VCON\\_READ\\_OP](#), [474](#)
  - [L4\\_VCON\\_SET\\_ATTR\\_OP](#), [474](#)
  - [L4\\_VCON\\_WRITE\\_OP](#), [474](#)
- [L4 kernel object type information](#), [280](#)
  - [kobject\\_typeid](#), [281](#)
- L4 Vbus functions, [487](#)
  - [l4vbus\\_assign\\_dma\\_domain](#), [489](#)
  - [L4vbus\\_dma\\_domain\\_assign\\_flags](#), [489](#)
  - [L4VBUS\\_DMAD\\_BIND](#), [489](#)
  - [L4VBUS\\_DMAD\\_KERNEL\\_DMA\\_SPACE](#), [489](#)
  - [L4VBUS\\_DMAD\\_L4RE\\_DMA\\_SPACE](#), [489](#)
  - [L4VBUS\\_DMAD\\_UNBIND](#), [489](#)
  - [l4vbus\\_get\\_adr](#), [490](#)
  - [l4vbus\\_get\\_device](#), [490](#)
  - [l4vbus\\_get\\_device\\_by\\_hid](#), [491](#)
  - [l4vbus\\_get\\_hid](#), [492](#)
  - [l4vbus\\_get\\_next\\_device](#), [493](#)
  - [l4vbus\\_get\\_resource](#), [493](#)
  - [l4vbus\\_is\\_compatible](#), [494](#)



- [l4vbus\\_release\\_ioport](#), 495
- [l4vbus\\_request\\_ioport](#), 496
- [l4vbus\\_vicu\\_get\\_cap](#), 496
- L4 VIRTIO Block Device, 484
  - [L4virtio\\_block\\_operations](#), 485
  - [L4VIRTIO\\_BLOCK\\_S\\_IOERR](#), 485
  - [L4VIRTIO\\_BLOCK\\_S\\_OK](#), 485
  - [L4VIRTIO\\_BLOCK\\_S\\_UNSUPP](#), 485
  - [L4virtio\\_block\\_status](#), 485
  - [L4VIRTIO\\_BLOCK\\_T\\_DISCARD](#), 485
  - [L4VIRTIO\\_BLOCK\\_T\\_FLUSH](#), 485
  - [L4VIRTIO\\_BLOCK\\_T\\_GET\\_ID](#), 485
  - [L4VIRTIO\\_BLOCK\\_T\\_IN](#), 485
  - [L4VIRTIO\\_BLOCK\\_T\\_OUT](#), 485
  - [L4VIRTIO\\_BLOCK\\_T\\_WRITE\\_ZEROES](#), 485
- L4 VIRTIO Input Device, 486
- L4 VIRTIO Interface, 475
- L4 VIRTIO Network Device, 486
- L4 VIRTIO Transport Layer, 475
  - [L4\\_virtio\\_cmd](#), 478
  - [L4\\_virtio\\_irq\\_status](#), 478
  - [L4\\_virtio\\_opcodes](#), 478
  - [L4VIRTIO\\_CMD\\_CFG\\_CHANGED](#), 478
  - [L4VIRTIO\\_CMD\\_CFG\\_QUEUE](#), 478
  - [L4VIRTIO\\_CMD\\_MASK](#), 478
  - [L4VIRTIO\\_CMD\\_NONE](#), 478
  - [L4VIRTIO\\_CMD\\_NOTIFY\\_QUEUE](#), 478
  - [L4VIRTIO\\_CMD\\_SET\\_STATUS](#), 478
  - [l4virtio\\_config\\_queue](#), 480
  - [l4virtio\\_config\\_queue\\_t](#), 477
  - [l4virtio\\_config\\_queues](#), 481
  - [l4virtio\\_device\\_config](#), 481
  - [l4virtio\\_device\\_config\\_ds](#), 481
  - [L4virtio\\_device\\_ids](#), 479
  - [l4virtio\\_device\\_notification\\_irq](#), 482
  - [L4virtio\\_device\\_status](#), 479
  - [L4virtio\\_feature\\_bits](#), 480
  - [L4VIRTIO\\_FEATURE\\_CMD\\_CONFIG](#), 480
  - [L4VIRTIO\\_FEATURE\\_VERSION\\_1](#), 480
  - [L4VIRTIO\\_ID\\_9P](#), 479
  - [L4VIRTIO\\_ID\\_BALLOON](#), 479
  - [L4VIRTIO\\_ID\\_BLOCK](#), 479
  - [L4VIRTIO\\_ID\\_CAIF](#), 479
  - [L4VIRTIO\\_ID\\_CAN](#), 479
  - [L4VIRTIO\\_ID\\_CONSOLE](#), 479
  - [L4VIRTIO\\_ID\\_CRYPTIO](#), 479
  - [L4VIRTIO\\_ID\\_FS](#), 479
  - [L4VIRTIO\\_ID\\_GPIO](#), 479
  - [L4VIRTIO\\_ID\\_GPU](#), 479
  - [L4VIRTIO\\_ID\\_I2C](#), 479
  - [L4VIRTIO\\_ID\\_INPUT](#), 479
  - [L4VIRTIO\\_ID\\_NET](#), 479
  - [L4VIRTIO\\_ID\\_RNG](#), 479
  - [L4VIRTIO\\_ID\\_RPMMSG](#), 479
  - [L4VIRTIO\\_ID\\_RPROC\\_SERIAL](#), 479
  - [L4VIRTIO\\_ID\\_SCMI](#), 479
  - [L4VIRTIO\\_ID\\_SCSI](#), 479
  - [L4VIRTIO\\_ID\\_SOCKET](#), 479
  - [L4VIRTIO\\_ID\\_SPI](#), 479
  - [L4VIRTIO\\_ID\\_VSOCKET](#), 479
  - [L4VIRTIO\\_ID\\_WATCHDOG](#), 479
  - [L4VIRTIO\\_IRQ\\_STATUS\\_CONFIG](#), 478
  - [L4VIRTIO\\_IRQ\\_STATUS\\_VRING](#), 478
  - [L4VIRTIO\\_OP\\_CONFIG\\_QUEUE](#), 479
  - [L4VIRTIO\\_OP\\_DEVICE\\_CONFIG](#), 479
  - [L4VIRTIO\\_OP\\_GET\\_DEVICE\\_IRQ](#), 479
  - [L4VIRTIO\\_OP\\_REGISTER\\_DS](#), 479
  - [L4VIRTIO\\_OP\\_SET\\_STATUS](#), 478
  - [l4virtio\\_register\\_ds](#), 482
  - [l4virtio\\_set\\_status](#), 483
  - [L4VIRTIO\\_STATUS\\_ACKNOWLEDGE](#), 480
  - [L4VIRTIO\\_STATUS\\_DEVICE\\_NEEDS\\_RESET](#), 480
  - [L4VIRTIO\\_STATUS\\_DRIVER](#), 480
  - [L4VIRTIO\\_STATUS\\_DRIVER\\_OK](#), 480
  - [L4VIRTIO\\_STATUS\\_FAILED](#), 480
  - [L4VIRTIO\\_STATUS\\_FEATURES\\_OK](#), 480
- [l4/cxx/alloc.h](#), 2558, 2559
- [l4/cxx/arith](#), 2559
- [l4/cxx/atomic.h](#), 3304, 3305
- [l4/cxx/avl\\_map](#), 2560, 2562
- [l4/cxx/avl\\_set](#), 2563, 2565
- [l4/cxx/avl\\_tree](#), 2568, 2570
- [l4/cxx/basic\\_ostream](#), 2574, 2575
- [l4/cxx/basic\\_vector.h](#), 2578, 2579
- [l4/cxx/bitfield](#), 2579
- [l4/cxx/bitmap](#), 2581
- [l4/cxx/bits/bst.h](#), 2584, 2586
- [l4/cxx/bits/bst\\_base.h](#), 2588, 2590
- [l4/cxx/bits/bst\\_iter.h](#), 2591, 2593
- [l4/cxx/bits/list\\_basics.h](#), 2594
- [l4/cxx/bits/smart\\_ptr\\_list.h](#), 2596, 2597
- [l4/cxx/bits/type\\_traits.h](#), 2599
- [l4/cxx/dlist](#), 2602
- [l4/cxx/elide\\_dtor](#), 2607
- [l4/cxx/exceptions](#), 2608, 2609
- [l4/cxx/hlist](#), 2612
- [l4/cxx/iostream](#), 2614
- [l4/cxx/ipc\\_helper](#), 2615, 2616
- [l4/cxx/ipc\\_server](#), 3096, 3098
- [l4/cxx/ipc\\_stream](#), 2616, 2626
- [l4/cxx/ipc\\_timeout\\_queue](#), 2634
- [l4/cxx/l4iostream](#), 2636, 2637
- [l4/cxx/l4types.h](#), 2637, 2638
- [l4/cxx/list](#), 2638
- [l4/cxx/list\\_alloc](#), 2642
- [l4/cxx/lock\\_guard.h](#), 2648
- [l4/cxx/main\\_thread](#), 2649, 2650
- [l4/cxx/minmax](#), 2651
- [l4/cxx/numeric](#), 2652
- [l4/cxx/observer](#), 2652
- [l4/cxx/pair](#), 2653, 2654
- [l4/cxx/ref\\_ptr](#), 2655
- [l4/cxx/ref\\_ptr\\_list](#), 2658, 2659
- [l4/cxx/slab\\_alloc](#), 2660
- [l4/cxx/slist](#), 2663

l4/cxx/static\_container, 2666  
l4/cxx/static\_vector, 2666  
l4/cxx/std\_alloc, 2667  
l4/cxx/std\_ops, 2668  
l4/cxx/string, 2668  
l4/cxx/string.h, 2671, 2672  
l4/cxx/thread, 3258, 3259  
l4/cxx/type\_list, 2673  
l4/cxx/type\_traits, 2673  
l4/cxx/unique\_ptr, 2678  
l4/cxx/unique\_ptr\_list, 2679, 2681  
l4/cxx/utills, 2681  
l4/cxx/weak\_ref, 2681  
l4/irq/irq.h, 2686, 2687  
l4/l4re\_vfs/backend, 2694  
l4/l4re\_vfs/impl/default\_ops\_impl.h, 2697  
l4/l4re\_vfs/impl/fd\_store.h, 2698  
l4/l4re\_vfs/impl/fd\_store\_impl.h, 2699  
l4/l4re\_vfs/impl/ns\_fs.h, 2699  
l4/l4re\_vfs/impl/ns\_fs\_impl.h, 2700  
l4/l4re\_vfs/impl/ro\_file.h, 2705  
l4/l4re\_vfs/impl/ro\_file\_impl.h, 2705  
l4/l4re\_vfs/impl/vcon\_stream.h, 2707  
l4/l4re\_vfs/impl/vcon\_stream\_impl.h, 2707  
l4/l4re\_vfs/impl/vfs\_impl.h, 2710  
l4/l4re\_vfs/vfs.h, 2722  
l4/l4virtio/client/l4virtio, 2734  
l4/l4virtio/client/virtio-block, 2753  
l4/l4virtio/client/virtio-net, 2731  
l4/l4virtio/l4virtio, 2736  
l4/l4virtio/server/l4virtio, 2738  
l4/l4virtio/server/virtio, 2749  
l4/l4virtio/server/virtio-block, 2757  
l4/l4virtio/server/virtio-console, 2763  
l4/l4virtio/server/virtio-console-device, 2769  
l4/l4virtio/server/virtio-gpio-device, 2773  
l4/l4virtio/server/virtio-i2c-device, 2778  
l4/l4virtio/server/virtio-rng-device, 2783  
l4/l4virtio/server/virtio-scmi-device, 2785  
l4/l4virtio/server/virtio-spi-device, 2794  
l4/l4virtio/virtio.h, 2799  
l4/l4virtio/virtio\_block.h, 2802  
l4/l4virtio/virtio\_input.h, 2803  
l4/l4virtio/virtio\_net.h, 2445  
l4/l4virtio/virtqueue, 2803  
l4/libedid/edid.h, 2808, 2809  
l4/re/c/dataspace.h, 2809, 2811  
l4/re/c/debug.h, 2405, 2406  
l4/re/c/dma\_space.h, 2812, 2814  
l4/re/c/event.h, 2815, 2816  
l4/re/c/event\_buffer.h, 2819  
l4/re/c/inhibitor.h, 2819, 2822  
l4/re/c/log.h, 2823  
l4/re/c/mem\_alloc.h, 2824, 2825  
l4/re/c/namespace.h, 2826, 2827  
l4/re/c/parent.h, 2827, 2829  
l4/re/c/rm.h, 2829, 2831  
l4/re/c/util/cap\_alloc.h, 2833, 2834  
l4/re/c/util/kumem\_alloc.h, 2835, 2836  
l4/re/c/util/video/goos\_fb.h, 2837  
l4/re/c/video/colors.h, 2838, 2840  
l4/re/c/video/goos.h, 2840, 2842  
l4/re/c/video/view.h, 2843, 2845  
l4/re/cap\_alloc, 2911, 2912  
l4/re/console, 2846  
l4/re/consts, 3068, 3069  
l4/re/consts.h, 3056, 3058  
l4/re/dataspace, 2846, 2847  
l4/re/dataspace-sys.h, 2849, 2850  
l4/re/dbg\_events, 2850  
l4/re/debug, 2927, 2929  
l4/re/dma\_space, 2850, 2852  
l4/re/elf\_aux.h, 2853, 2854  
l4/re/env, 2855, 2856  
l4/re/env.h, 2857, 2859  
l4/re/error\_helper, 2861, 2862  
l4/re/event, 2932  
l4/re/event-sys.h, 2864  
l4/re/event.h, 2817, 2818  
l4/re/event\_enums.h, 2864  
l4/re/impl/dataspace\_impl.h, 2870, 2871  
l4/re/impl/mem\_alloc\_impl.h, 2873, 2874  
l4/re/impl/namespace\_impl.h, 2874, 2875  
l4/re/impl/rm\_impl.h, 2877, 2878  
l4/re/inhibitor, 2879  
l4/re/inhibitor-sys.h, 2879  
l4/re/itas, 2880  
l4/re/l4aux.h, 2881, 2882  
l4/re/log, 2882, 2883  
l4/re/log-sys.h, 2884  
l4/re/mem\_alloc, 2884, 2886  
l4/re/mem\_alloc-sys.h, 2887  
l4/re/mmio\_space, 2888, 2889  
l4/re/namespace, 2889, 2891  
l4/re/namespace-sys.h, 2892, 2893  
l4/re/parent, 2893, 2894  
l4/re/parent-sys.h, 2895  
l4/re/protocols.h, 2895, 2896  
l4/re/random, 2896, 2898  
l4/re/remote\_access, 2898  
l4/re/rm, 2899, 2900  
l4/re/rm-sys.h, 2904, 2905  
l4/re/shared\_cap, 2964, 2966  
l4/re/unique\_cap, 2969, 2970  
l4/re/util/bitmap\_cap\_alloc, 2905, 2906  
l4/re/util/br\_manager, 2907  
l4/re/util/cap, 2909, 2910  
l4/re/util/cap\_alloc, 2914, 2916  
l4/re/util/cap\_alloc\_impl.h, 2917, 2918  
l4/re/util/counting\_cap\_alloc, 2919, 2921  
l4/re/util/dataspace\_svr, 2924  
l4/re/util/debug, 2929  
l4/re/util/env\_ns, 2931  
l4/re/util/event, 2934, 2935  
l4/re/util/event\_buffer, 2937  
l4/re/util/event\_svr, 2938



l4/re/util/icu\_svr, 2939  
l4/re/util/item\_alloc, 2941, 2943  
l4/re/util/kumem\_alloc, 2944, 2945  
l4/re/util/meta, 3213  
l4/re/util/name\_space\_svr, 2945  
l4/re/util/object\_registry, 2951  
l4/re/util/poll\_timeout\_kipclock, 2953  
l4/re/util/region\_mapping, 2954, 2955  
l4/re/util/region\_mapping\_svr, 2961  
l4/re/util/shared\_cap, 2966, 2968  
l4/re/util/unique\_cap, 2971, 2972  
l4/re/util/vcon\_svr, 2973  
l4/re/util/video/goos\_fb, 2974  
l4/re/util/video/goos\_svr, 2976  
l4/re/video/colors, 2977  
l4/re/video/goos, 2979  
l4/re/video/goos-sys.h, 2982, 2983  
l4/re/video/view, 2983  
l4/shmc/ringbuf.h, 2983, 2990  
l4/shmc/shmc.h, 2992, 2995  
l4/sigma0/sigma0.h, 2997, 2999  
l4/sys/\_\_kernel\_object\_impl.h, 3001  
l4/sys/\_\_ktrace-impl.h, 3001, 3002  
l4/sys/\_\_l4\_page.h, 3003  
l4/sys/\_\_platform\_control-arm.h, 3007  
l4/sys/\_\_task-arm.h, 3008  
l4/sys/\_\_timeout.h, 3008  
l4/sys/\_\_typeinfo.h, 3011, 3013  
l4/sys/\_\_vcpu-arm.h, 3023  
l4/sys/\_\_vm-svm.h, 3024  
l4/sys/\_\_vm-vmx.h, 3026  
l4/sys/arm\_smccc, 3032, 3033  
l4/sys/arm\_smccc.h, 3033, 3036  
l4/sys/assert.h, 3298, 3300  
l4/sys/cache.h, 3043, 3044  
l4/sys/capability, 3046, 3048  
l4/sys/compiler.h, 3049, 3051  
l4/sys/consts.h, 3058, 3063  
l4/sys/cxx/capability.h, 3065  
l4/sys/cxx/consts, 3069  
l4/sys/cxx/ipc\_array, 3070  
l4/sys/cxx/ipc\_basics, 3073  
l4/sys/cxx/ipc\_client, 3077, 3079  
l4/sys/cxx/ipc\_epiface, 3079  
l4/sys/cxx/ipc\_iface, 3083, 3090  
l4/sys/cxx/ipc\_legacy, 3095  
l4/sys/cxx/ipc\_ret\_array, 3095  
l4/sys/cxx/ipc\_server, 3098  
l4/sys/cxx/ipc\_server\_loop, 3103  
l4/sys/cxx/ipc\_string, 3106  
l4/sys/cxx/ipc\_types, 3107, 3109  
l4/sys/cxx/ipc\_varg, 3116  
l4/sys/cxx/limits, 3121  
l4/sys/cxx/smart\_capability\_1x, 3123, 3124  
l4/sys/cxx/types, 3126, 3128  
l4/sys/debugger, 3132, 3133  
l4/sys/debugger.h, 3133, 3136  
l4/sys/err.h, 3139, 3141  
l4/sys/exception, 3141, 3143  
l4/sys/factory, 3143, 3144  
l4/sys/factory.h, 3146, 3148  
l4/sys/icu, 3153, 3154  
l4/sys/icu.h, 3154, 3157  
l4/sys/iommu, 3160  
l4/sys/ipc.h, 3162, 3165  
l4/sys/ipc\_gate, 3170, 3172  
l4/sys/ipc\_gate.h, 3172, 3174  
l4/sys/irq, 3175, 3177  
l4/sys/irq.h, 2688, 2690  
l4/sys/kdebug.h, 3179, 3194  
l4/sys/kdump.h, 3196, 3198  
l4/sys/kernel\_object.h, 3198, 3199  
l4/sys/kip, 3200, 3201  
l4/sys/kip.h, 3343, 3346  
l4/sys/kobject, 3203  
l4/sys/ktrace.h, 3203, 3205  
l4/sys/l4int.h, 3208, 3209  
l4/sys/memdesc.h, 3210, 3212  
l4/sys/meta, 3214, 3215  
l4/sys/obj\_info.h, 3215, 3218  
l4/sys/pager, 3219, 3221  
l4/sys/platform\_control, 3221, 3223  
l4/sys/platform\_control.h, 3224, 3225  
l4/sys/rcv\_endpoint, 3228, 3229  
l4/sys/rcv\_endpoint.h, 3229, 3231  
l4/sys/scheduler, 3232, 3233  
l4/sys/scheduler.h, 3234, 3237  
l4/sys/semaphore, 3239, 3241  
l4/sys/semaphore.h, 3241, 3243  
l4/sys/smart\_capability, 3244, 3245  
l4/sys/snd\_destination, 3247, 3249  
l4/sys/snd\_destination.h, 3249, 3250  
l4/sys/task, 3250, 3252  
l4/sys/task.h, 3253, 3255  
l4/sys/thread, 3260, 3261  
l4/sys/thread.h, 2526, 2529  
l4/sys/thread\_group, 3262, 3263  
l4/sys/thread\_group.h, 3264, 3265  
l4/sys/typeinfo\_svr, 3266, 3267  
l4/sys/types.h, 3268, 3271  
l4/sys/utcb.h, 3281, 3283  
l4/sys/vcon, 3287, 3289  
l4/sys/vcon.h, 3289, 3292  
l4/sys/vcpu, 3393, 3395  
l4/sys/vcpu\_context, 3295, 3296  
l4/sys/vcpu\_context.h, 3296  
l4/sys/vm, 3296, 3298  
l4/util/assert.h, 3301, 3302  
l4/util/atomic.h, 3306, 3309  
l4/util/backtrace.h, 3313, 3315  
l4/util/base64.h, 3315, 3317  
l4/util/bitops.h, 3317, 3319  
l4/util/elf.h, 3322, 3329  
l4/util/getopt.h, 3339, 3340  
l4/util/keymap.h, 3341, 3342  
l4/util/kip.h, 3348

- l4/util/kprintf.h, 3349, 3350
- l4/util/l4\_macros.h, 2522, 2523
- l4/util/l4mod.h, 3350, 3351
- l4/util/list\_alloc.h, 3352, 3355
- l4/util/lock.h, 3355, 3356
- l4/util/mb\_info.h, 3357, 3361
- l4/util/parse\_cmd.h, 3365, 3366
- l4/util/printf\_helpers.h, 3367
- l4/util/rand.h, 3367, 3368
- l4/util/splitlog2.h, 3368, 3369
- l4/util/thread.h, 2536, 2538
- l4/util/util.h, 3370
- l4/vbus/vbus, 3371
- l4/vbus/vbus.h, 3373, 3375
- l4/vbus/vbus\_generic, 3376
- l4/vbus/vbus\_gpio, 3377
- l4/vbus/vbus\_gpio-ops.h, 3378
- l4/vbus/vbus\_gpio.h, 3378
- l4/vbus/vbus\_i2c.h, 3379
- l4/vbus/vbus\_inhibitor.h, 3380
- l4/vbus/vbus\_interfaces.h, 3380, 3383
- l4/vbus/vbus\_mcspi.h, 3383
- l4/vbus/vbus\_pci, 3384
- l4/vbus/vbus\_pci-ops.h, 3385
- l4/vbus/vbus\_pci.h, 3385
- l4/vbus/vbus\_pm-ops.h, 3386
- l4/vbus/vbus\_pm.h, 3386
- l4/vbus/vbus\_types.h, 3386, 3389
- l4/vbus/vdevice-ops.h, 3390
- l4/vcpu/vcpu, 3391
- l4/vcpu/vcpu.h, 3396, 3398
- L4::Alloc\_list, 991
- L4::Arm\_smccc, 992
  - call, 992
- L4::Base\_exception, 994
- L4::Basic\_registry, 996
  - dispatch, 997
  - find, 998
- L4::Bounds\_error, 999
- L4::Cap< T >, 1002
  - Cap, 1006
  - check\_castable\_from, 1007
  - check\_convertible\_from, 1007
  - copy, 1007
  - move, 1008
- L4::Cap\_base, 1008
  - cap, 1013
  - Cap\_base, 1011, 1012
  - Cap\_type, 1011
  - copy, 1014
  - fpage, 1015
  - Invalid, 1011
  - is\_valid, 1016
  - move, 1017
  - No\_init, 1011
  - No\_init\_type, 1011
  - snd\_base, 1018
  - validate, 1019, 1020
- L4::Com\_error, 1021
  - Com\_error, 1024
- L4::Debugger, 1024
  - add\_image\_info, 1028
  - get\_object\_name, 1028
  - global\_id, 1029
  - kobj\_to\_id, 1030
  - query\_log\_name, 1030
  - query\_log\_typeid, 1031
  - query\_object\_name, 1032
  - set\_object\_name, 1033
  - switch\_log, 1033
- L4::Element\_already\_exists, 1034
- L4::Element\_not\_found, 1038
- L4::Epiface, 1041
  - dispatch, 1042
  - get\_buffer\_demand, 1043
  - obj\_cap, 1043
  - server\_iface, 1044
  - set\_server, 1045
- L4::Epiface\_t< Derived, IFACE, BASE, bool >, 1046
  - dispatch, 1049
- L4::Epiface\_t0< RPC\_IFACE, BASE >, 1049
  - obj\_cap, 1052
- L4::Exception, 1052
  - exception, 1053
- L4::Exception\_tracer, 1054
- L4::Factory, 1055
  - create, 1059, 1060
  - create\_factory, 1061
  - create\_gate, 1063
  - create\_task, 1064
  - create\_thread\_group, 1065
- L4::Factory::Lstr, 1066
  - Lstr, 1067
- L4::Factory::Nil, 1068
- L4::Factory::S, 1068
  - ~S, 1070
  - operator l4\_msgtag\_t, 1071
  - operator<<, 1071, 1072
  - put, 1073, 1074
  - S, 1070
- L4::lcu, 1075
  - bind, 1079
  - info, 1080
  - mask, 1081
  - msi\_info, 1082
  - set\_mode, 1083
  - unbind, 1084
- L4::lcu::Info, 1085
- L4::Invalid\_capability, 1087
  - cap, 1090
  - Invalid\_capability, 1089
- L4::lo\_pager, 1090
  - io\_page\_fault, 1093
- L4::lommu, 1093
  - bind, 1096
  - unbind, 1096

- L4::IOModifier, [1098](#)
- L4::lpc, [742](#)
  - buf\_cp\_in, [744](#)
  - buf\_cp\_out, [745](#)
  - buf\_in, [745](#)
  - make\_cap, [746](#)
  - make\_cap\_full, [747](#)
  - make\_cap\_rw, [747](#)
  - make\_cap\_rws, [748](#)
  - msg\_ptr, [749](#)
  - read, [749](#)
  - str\_cp\_in, [749](#)
- L4::lpc::Array< ELEM\_TYPE, LEN\_TYPE >, [1098](#)
- L4::lpc::Array\_in\_buf< ELEM\_TYPE, LEN\_TYPE, MAX >, [1101](#)
- L4::lpc::Array\_ref< ELEM\_TYPE, LEN\_TYPE >, [1104](#)
- L4::lpc::As\_value< T >, [1105](#)
- L4::lpc::Call, [1106](#)
- L4::lpc::Call\_t< RIGHTS >, [1107](#)
- L4::lpc::Call\_zero\_send\_timeout, [1108](#)
- L4::lpc::Cap< T >, [1109](#)
  - Cap, [1113](#)
  - Cap\_mask, [1112](#)
  - from\_ci, [1113](#)
  - Rights\_mask, [1112](#)
- L4::lpc::Gen\_fpage, [1113](#)
  - Io, [1116](#)
  - Memory, [1116](#)
  - Obj, [1116](#)
  - Special, [1116](#)
  - Type, [1115](#)
- L4::lpc::In\_out< T >, [1116](#)
- L4::lpc::Iostream, [1117](#)
  - call, [1121](#)
  - get, [1122](#), [1123](#)
  - lostream, [1121](#)
  - put, [1123](#), [1124](#)
  - reply\_and\_wait, [1124](#), [1125](#)
  - reset, [1126](#)
- L4::lpc::Istream, [1127](#)
  - get, [1131](#), [1132](#)
  - Istream, [1130](#)
  - receive, [1133](#)
  - reset, [1134](#)
  - skip, [1135](#)
  - tag, [1135](#)
  - wait, [1136](#), [1137](#)
- L4::lpc::Msg, [750](#)
  - align\_to, [752](#), [753](#)
  - Br\_bytes, [752](#)
  - check\_size, [753](#), [754](#)
  - Item\_bytes, [752](#)
  - Item\_words, [752](#)
  - Mr\_bytes, [752](#)
  - Mr\_words, [752](#)
  - msg\_add, [755](#)
  - msg\_get, [756](#)
  - Word\_bytes, [752](#)
- L4::lpc::Msg::CInt\_val\_ops< MTYPE, DIR, CLASS >, [1138](#)
- L4::lpc::Msg::Cls\_buffer, [1139](#)
- L4::lpc::Msg::Cls\_data, [1141](#)
- L4::lpc::Msg::Cls\_item, [1142](#)
- L4::lpc::Msg::Dir\_in, [1143](#)
- L4::lpc::Msg::Dir\_out, [1144](#)
- L4::lpc::Msg::Do\_in\_data, [1145](#)
- L4::lpc::Msg::Do\_in\_items, [1146](#)
- L4::lpc::Msg::Do\_out\_data, [1147](#)
- L4::lpc::Msg::Do\_out\_items, [1148](#)
- L4::lpc::Msg::Do\_rcv\_buffers, [1150](#)
- L4::lpc::Msg::Elem< Array< A, LEN > >, [1152](#)
- L4::lpc::Msg::Elem< Array< A, LEN > & >, [1151](#)
- L4::lpc::Msg::Elem< Array\_ref< A, LEN > & >, [1153](#)
- L4::lpc::Msg::False, [1154](#)
- L4::lpc::Msg::Is\_valid\_rpc\_type< T >, [1156](#)
- L4::lpc::Msg::Svr\_arg\_pack< IPC\_TYPE >, [1158](#)
- L4::lpc::Msg::Svr\_val\_ops< MTYPE, DIR, CLASS >, [1158](#)
- L4::lpc::Msg::True, [1159](#)
- L4::lpc::Msg\_ptr< T >, [1162](#)
  - Msg\_ptr, [1163](#)
- L4::lpc::Opt< T >, [1163](#)
- L4::lpc::Ostream, [1165](#)
  - put, [1168](#), [1169](#)
  - send, [1169](#)
  - tag, [1170](#)
- L4::lpc::Out< T >, [1171](#)
- L4::lpc::Rcv\_fpage, [1172](#)
  - io, [1176](#)
  - mem, [1176](#)
  - obj, [1177](#)
  - Rcv\_fpage, [1175](#)
  - rcv\_task, [1178](#)
- L4::lpc::Ret\_array< T >, [1179](#)
- L4::lpc::Send\_only, [1180](#)
- L4::lpc::Small\_buf, [1181](#)
  - Small\_buf, [1182](#)
- L4::lpc::Snd\_fpage, [1183](#)
  - Buffered, [1186](#)
  - Cached, [1186](#)
  - Cacheopt, [1186](#)
  - cap\_received, [1189](#)
  - Compound, [1187](#)
  - Continue, [1186](#)
  - Grant, [1187](#)
  - id\_received, [1189](#)
  - io, [1189](#)
  - is\_compound, [1190](#)
  - Last, [1187](#)
  - local\_id\_received, [1190](#)
  - Map, [1187](#)
  - Map\_type, [1187](#)
  - mem, [1190](#)
  - More, [1187](#)
  - None, [1186](#)
  - obj, [1191](#)

- Single, 1187
- Snd\_fpage, 1187, 1188
- Uncached, 1186
- L4::lpc::Str\_cp\_in< T >, 1193
  - Str\_cp\_in, 1194
- L4::lpc::Varg, 1194
  - data, 1196
  - get\_value, 1196
  - is\_nil, 1196
  - is\_of, 1197
  - is\_of\_int, 1198
  - length, 1198
  - tag, 1199
  - type, 1199
  - value, 1199
- L4::lpc::Varg\_list< MAX >, 1200
- L4::lpc::Varg\_list\_ref, 1203
  - Varg\_list\_ref, 1205
- L4::lpc::Varg\_list\_ref::iterator, 1205
- L4::lpc\_gate, 1207
  - get\_infos, 1211
- L4::lpc\_svr, 757
- L4::lpc\_svr::Br\_manager\_no\_buffers, 1212
  - alloc\_buffer\_demand, 1215
- L4::lpc\_svr::Compound\_reply, 1216
- L4::lpc\_svr::Dbg\_dispatch< R, Exc, Printer >, 1218
- L4::lpc\_svr::Default\_loop\_hooks, 1220
- L4::lpc\_svr::Default\_setup\_wait, 1223
- L4::lpc\_svr::Default\_timeout, 1224
- L4::lpc\_svr::Direct\_dispatch< R >, 1226
- L4::lpc\_svr::Direct\_dispatch< R \* >, 1228
- L4::lpc\_svr::Exc\_dispatch< R, Exc >, 1230
- L4::lpc\_svr::Ignore\_errors, 1232
- L4::lpc\_svr::Server\_iface, 1233
  - add\_timeout, 1236
  - alloc\_buffer\_demand, 1236
  - get\_rcv\_cap, 1236
  - rcv\_cap, 1237, 1238
  - realloc\_rcv\_cap, 1239
  - remove\_timeout, 1239
- L4::lpc\_svr::Timeout, 1240
  - expired, 1243
  - timeout, 1243
- L4::lpc\_svr::Timeout\_queue, 1244
  - add, 1245
  - handle\_expired\_timeouts, 1245
  - next\_timeout, 1245
  - remove, 1246
  - timeout\_expired, 1246
- L4::lpc\_svr::Timeout\_queue\_hooks< HOOKS, BR\_MAN >, 1247
  - add\_timeout, 1251
  - remove\_timeout, 1251
- L4::lrq, 1252
  - bind\_vcpu, 1258
  - detach, 1259
  - receive, 1260
  - unmask, 1260
  - wait, 1261
- L4::lrq\_eoi, 1262
  - unmask, 1264
- L4::lrq\_handler\_object, 1265
- L4::lrqep\_t< Derived, BASE, bool >, 1269
  - dispatch, 1272
  - obj\_cap, 1272
- L4::Kip::Mem\_desc, 1273
  - all, 1278
  - Arch, 1276
  - Arch\_acpi\_nvs, 1276
  - Arch\_acpi\_tables, 1276
  - Arch\_sub\_type\_common, 1275
  - Bootloader, 1276
  - Conventional, 1276
  - count, 1278, 1279
  - Dedicated, 1276
  - end, 1280
  - first, 1280
  - Info, 1276
  - Info\_acpi\_rsd, 1276
  - Info\_sub\_type, 1276
  - is\_virtual, 1281
  - Mem\_desc, 1277
  - Mem\_type, 1276
  - Reserved, 1276
  - Reserved\_heap, 1276
  - Reserved\_kernel, 1276
  - Reserved\_mmio, 1276
  - set, 1282
  - Shared, 1276
  - size, 1282
  - start, 1283
  - sub\_type, 1283
  - type, 1284
  - Undefined, 1276
- L4::Kobject, 1284
  - cap, 1285
  - dec\_refcnt, 1287
- L4::Kobject\_2t< Derived, Base1, Base2, PROTO, S\_DEMAND >, 1288
  - \_\_iface, 1290
  - \_\_iface\_list, 1290
  - \_\_check\_protocols\_\_, 1291
  - c, 1291
  - Class, 1291
- L4::Kobject\_3t< Derived, Base1, Base2, Base3, PROTO, S\_DEMAND >, 1292
  - \_\_iface, 1294
  - \_\_iface\_list, 1294
  - \_\_check\_protocols\_\_, 1295
  - c, 1295
  - Class, 1294
- L4::Kobject\_demand< T >, 1295
- L4::Kobject\_t< Derived, Base, PROTO, S\_DEMAND >, 1296
- L4::Kobject\_typeid< T >, 1298
  - Demand, 1299

- demand, [1300](#)
- id, [1300](#)
- proto\_dispatch, [1300](#)
- L4::Kobject\_typeid< void >, [1302](#)
- demand, [1303](#)
- id, [1304](#)
- proto\_dispatch, [1304](#)
- L4::Kobject\_x< Derived, ARGS >, [1305](#)
- L4::Lock\_guard, [1306](#)
- ~Lock\_guard, [1308](#)
- Lock\_guard, [1307](#)
- operator=, [1308](#)
- status, [1308](#)
- L4::Meta, [1309](#)
- interface, [1313](#)
- num\_interfaces, [1313](#)
- supports, [1314](#)
- L4::Out\_of\_memory, [1315](#)
- L4::Pager, [1319](#)
- page\_fault, [1321](#)
- L4::Platform\_control, [1322](#)
- cpu\_allow\_shutdown, [1326](#)
- cpu\_disable, [1326](#)
- cpu\_enable, [1327](#)
- system\_shutdown, [1328](#)
- system\_suspend, [1329](#)
- L4::Poll\_timeout\_counter, [1330](#)
- Poll\_timeout\_counter, [1332](#)
- set, [1332](#)
- timed\_out, [1332](#)
- L4::Poll\_timeout\_kipclock, [1333](#)
- Poll\_timeout\_kipclock, [1334](#)
- set, [1335](#)
- test, [1335](#)
- timed\_out, [1336](#)
- L4::Proto\_t< P >, [1337](#)
- L4::Rcv\_endpoint, [1337](#)
- bind\_snd\_destination, [1341](#)
- bind\_thread, [1341](#)
- L4::Registry\_iface, [1343](#)
- register\_irq\_obj, [1345](#)
- register\_obj, [1345](#), [1346](#)
- unregister\_obj, [1347](#)
- L4::Runtime\_error, [1348](#)
- err\_no, [1351](#)
- extra\_str, [1351](#)
- Runtime\_error, [1350](#)
- L4::Scheduler, [1352](#)
- idle\_time, [1357](#)
- info, [1357](#)
- is\_online, [1358](#)
- run\_thread, [1359](#)
- L4::Semaphore, [1361](#)
- down, [1364](#)
- up, [1365](#)
- L4::Server< LOOP\_HOOKS >, [1366](#)
- internal\_loop, [1370](#)
- loop, [1371](#)
- loop\_dbg, [1371](#)
- Server, [1370](#)
- L4::Server\_object, [1372](#)
- dispatch, [1375](#), [1376](#)
- L4::Server\_object\_t< IFACE, BASE >, [1377](#)
- dispatch\_meta\_request, [1381](#)
- get\_buffer\_demand, [1381](#)
- proto\_dispatch, [1381](#)
- L4::Server\_object\_x< Derived, IFACE, BASE >, [1382](#)
- L4::Smart\_cap< T, SMART >, [1386](#)
- Smart\_cap, [1390](#)
- L4::String, [1390](#)
- L4::Task, [1391](#)
- add\_ku\_mem, [1395](#)
- cap\_equal, [1396](#)
- cap\_valid, [1397](#)
- delete\_obj, [1398](#)
- map, [1399](#)
- release\_cap, [1400](#)
- unmap, [1401](#)
- unmap\_batch, [1402](#)
- L4::Thread, [1404](#)
- control, [1407](#)
- ex\_regs, [1408](#), [1409](#)
- modify\_senders, [1410](#)
- register\_del\_irq, [1411](#)
- register\_doorbell\_irq, [1412](#)
- stats\_time, [1413](#)
- switch\_to, [1414](#)
- vcpu\_control, [1415](#)
- vcpu\_control\_ext, [1416](#)
- vcpu\_resume\_commit, [1417](#)
- vcpu\_resume\_start, [1418](#)
- L4::Thread::Attr, [1419](#)
- alien, [1421](#)
- Attr, [1421](#)
- bind, [1421](#)
- exc\_handler, [1422](#)
- pager, [1423](#)
- L4::Thread::Modify\_senders, [1425](#)
- add, [1426](#)
- L4::Thread\_group, [1427](#)
- add, [1429](#)
- remove, [1430](#)
- L4::Triggerable, [1431](#)
- trigger, [1434](#)
- L4::Type\_info, [1435](#)
- L4::Type\_info::Demand, [1436](#)
- Demand, [1439](#)
- no\_demand, [1439](#)
- L4::Type\_info::Demand\_t< CAPS, FLAGS, MEM, PORTS >, [1440](#)
- Caps, [1443](#)
- Flags, [1443](#)
- Mem, [1443](#)
- Ports, [1443](#)
- L4::Type\_info::Demand\_union\_t< D1, D2 >, [1443](#)
- L4::Typeid, [758](#)

L4::Typeid::Detail::\_Rpc< OPCODE, O, Default\_op< R > >::Rpc< Y >, [1448](#)  
 L4::Typeid::Detail::\_Rpc< OPCODE, O, R, X... >, [1448](#)  
 L4::Typeid::Detail::\_Rpc< OPCODE, O, R, X... >::Rpc< Y >, [1451](#)  
 L4::Typeid::Detail::\_Rpc< OPCODE, O, X >, [1447](#)  
 L4::Typeid::Detail::Rpc\_end, [1452](#)  
 L4::Typeid::P\_dispatch< LIST >, [1452](#)  
 L4::Typeid::Raw\_ipc< CLASS >, [1453](#)  
 L4::Typeid::Rpc\_nocode< OPERATION >, [1455](#)  
 L4::Typeid::Rpc< RPCS >, [1457](#)  
 L4::Typeid::Rpc\_code< OPCODE\_TYPE >, [1459](#)  
 L4::Typeid::Rpc\_code< OPCODE\_TYPE >::F< RPCS >, [1460](#)  
 L4::Typeid::Rpc\_sys< ARG >, [1463](#)  
 L4::Types, [758](#)  
     declval, [760](#)  
 L4::Types::\_\_Add\_rvalue\_reference\_helper< T, type-name >, [1465](#)  
 L4::Types::\_\_Add\_rvalue\_reference\_helper< T, Void< T && > >, [1466](#)  
 L4::Types::\_\_Underlying\_type\_helper< T, bool >, [1468](#)  
 L4::Types::\_\_Underlying\_type\_helper< T, false >, [1469](#)  
 L4::Types::Add\_rvalue\_reference< T >, [1471](#)  
 L4::Types::Bool< V >, [1472](#)  
 L4::Types::False, [1473](#)  
 L4::Types::Flags< BITS\_ENUM, UNDERLYING >, [1476](#)  
     clear, [1480](#)  
     Flags, [1479](#)  
     from\_raw, [1480](#)  
     None, [1479](#)  
     None\_type, [1479](#)  
 L4::Types::Flags\_ops\_t< DT >, [1480](#)  
 L4::Types::Flags\_t< DT, T >, [1483](#)  
 L4::Types::Int\_for\_size< SIZE, bool >, [1487](#)  
 L4::Types::Int\_for\_type< T >, [1488](#)  
 L4::Types::Integral\_constant< T, Value >, [1489](#)  
 L4::Types::ls\_enum< T >, [1490](#)  
 L4::Types::Same< A, B >, [1492](#)  
 L4::Types::True, [1494](#)  
 L4::Types::Underlying\_type< T >, [1497](#)  
 L4::Uart, [1498](#)  
     change\_mode, [1501](#)  
     char\_avail, [1501](#)  
     enable\_rx\_irq, [1501](#)  
     generic\_write, [1502](#)  
     get\_char, [1502](#)  
     mode, [1503](#)  
     rate, [1503](#)  
     shutdown, [1503](#)  
     startup, [1503](#)  
     write, [1504](#)  
 L4::Uart\_apb, [1505](#)  
     change\_mode, [1507](#)  
     char\_avail, [1508](#)  
     enable\_rx\_irq, [1508](#)  
     get\_char, [1508](#)  
     shutdown, [1509](#)  
     startup, [1509](#)  
     write, [1509](#)  
 L4::Unknown\_error, [1510](#)  
 L4::Vcon, [1513](#)  
     get\_attr, [1518](#)  
     read, [1518](#)  
     read\_with\_flags, [1519](#)  
     send, [1520](#)  
     set\_attr, [1521](#)  
     write, [1522](#)  
 L4::Vm, [1523](#)  
 l4\_addr\_consts\_t  
     Memory related, [200](#)  
 l4\_align\_stack\_for\_direct\_fncall  
     Basic Macros, [156](#)  
 L4\_AMD64\_SEGMENT\_FS  
     segment.h, [2449](#)  
 L4\_AMD64\_SEGMENT\_GS  
     segment.h, [2449](#)  
 l4\_arm\_smccc\_call  
     arm\_smccc.h, [3034](#)  
 l4\_assert  
     assert.h, [3300](#)  
 L4\_BASE\_ARM\_SMCCC\_CAP  
     Capabilities, [439](#)  
 L4\_BASE\_CAPS\_LAST  
     Capabilities, [439](#)  
 L4\_BASE\_DEBUGGER\_CAP  
     Capabilities, [439](#)  
 L4\_BASE\_FACTORY\_CAP  
     Capabilities, [439](#)  
 L4\_BASE\_ICU\_CAP  
     Capabilities, [439](#)  
 L4\_BASE\_IOMMU\_CAP  
     Capabilities, [439](#)  
 L4\_BASE\_LOG\_CAP  
     Capabilities, [439](#)  
 L4\_BASE\_PAGER\_CAP  
     Capabilities, [439](#)  
 L4\_BASE\_SCHEDULER\_CAP  
     Capabilities, [439](#)  
 L4\_BASE\_TASK\_CAP  
     Capabilities, [439](#)  
 L4\_BASE\_THREAD\_CAP  
     Capabilities, [439](#)  
 L4\_BDR\_IO\_SHIFT  
     Buffer Registers (BRs), [270](#)  
 L4\_BDR\_MEM\_SHIFT  
     Buffer Registers (BRs), [270](#)  
 L4\_BDR\_OBJ\_SHIFT  
     Buffer Registers (BRs), [270](#)  
 l4\_buf\_regs\_t, [1527](#)  
 l4\_buffer\_desc\_consts\_t  
     Buffer Registers (BRs), [270](#)  
 l4\_busy\_wait\_ns  
     Timestamp Counter, [652](#)

- [l4\\_busy\\_wait\\_us](#)
  - Timestamp Counter, [653](#)
- [l4\\_bytes\\_to\\_mwords](#)
  - Memory related, [201](#)
- [l4\\_cache\\_clean\\_data](#)
  - Cache Consistency, [193](#)
- [l4\\_cache\\_coherent](#)
  - Cache Consistency, [194](#)
- [l4\\_cache\\_dma\\_coherent](#)
  - Cache Consistency, [194](#)
- [l4\\_cache\\_flush\\_data](#)
  - Cache Consistency, [195](#)
- [l4\\_cache\\_inv\\_data](#)
  - Cache Consistency, [195](#)
- [l4\\_calibrate\\_tsc](#)
  - Timestamp Counter, [654](#)
- [L4\\_CAP\\_FPAGE\\_D](#)
  - Flexpages, [177](#)
- [L4\\_CAP\\_FPAGE\\_R](#)
  - Flexpages, [176](#)
- [L4\\_cap\\_fpage\\_rights](#)
  - Flexpages, [176](#)
- [L4\\_CAP\\_FPAGE\\_RO](#)
  - Flexpages, [176](#)
- [L4\\_CAP\\_FPAGE\\_RS](#)
  - Flexpages, [177](#)
- [L4\\_CAP\\_FPAGE\\_RSD](#)
  - Flexpages, [177](#)
- [L4\\_CAP\\_FPAGE\\_RW](#)
  - Flexpages, [177](#)
- [L4\\_CAP\\_FPAGE\\_RWD](#)
  - Flexpages, [177](#)
- [L4\\_CAP\\_FPAGE\\_RWS](#)
  - Flexpages, [177](#)
- [L4\\_CAP\\_FPAGE\\_RWSD](#)
  - Flexpages, [177](#)
- [L4\\_CAP\\_FPAGE\\_S](#)
  - Flexpages, [176](#)
- [L4\\_CAP\\_FPAGE\\_W](#)
  - Flexpages, [176](#)
- [l4\\_cap\\_idx\\_t](#)
  - Capabilities, [438](#)
- [L4\\_CAP\\_SIZE](#)
  - consts.h, [3060](#)
- [l4\\_capability\\_equal](#)
  - Capabilities, [439](#)
- [l4\\_capability\\_next](#)
  - types.h, [3271](#)
- [l4\\_debugger\\_add\\_image\\_info](#)
  - Kernel Debugger, [162](#)
- [l4\\_debugger\\_get\\_object\\_name](#)
  - Kernel Debugger, [163](#)
- [l4\\_debugger\\_global\\_id](#)
  - Kernel Debugger, [164](#)
- [L4\\_DEBUGGER\\_GLOBAL\\_ID\\_GET\\_NAME\\_OP](#)
  - debugger.h, [3136](#)
- [L4\\_DEBUGGER\\_KOBJ\\_GET\\_GLOBAL\\_ID\\_OP](#)
  - debugger.h, [3135](#)
- [L4\\_DEBUGGER\\_KOBJ\\_GET\\_NAME\\_OP](#)
  - debugger.h, [3136](#)
- [L4\\_DEBUGGER\\_KOBJ\\_PTR\\_GET\\_GLOBAL\\_ID\\_OP](#)
  - debugger.h, [3135](#)
- [L4\\_DEBUGGER\\_KOBJ\\_SET\\_NAME\\_OP](#)
  - debugger.h, [3135](#)
- [l4\\_debugger\\_kobj\\_to\\_id](#)
  - Kernel Debugger, [164](#)
- [L4\\_DEBUGGER\\_LOG\\_QUERY\\_NAME\\_OP](#)
  - debugger.h, [3136](#)
- [L4\\_DEBUGGER\\_LOG\\_QUERY\\_TYPEID\\_OP](#)
  - debugger.h, [3135](#)
- [L4\\_DEBUGGER\\_LOG\\_SWITCH\\_OP](#)
  - debugger.h, [3135](#)
- [L4\\_DEBUGGER\\_OBJ\\_INFO\\_OP](#)
  - debugger.h, [3136](#)
- [l4\\_debugger\\_query\\_log\\_name](#)
  - Kernel Debugger, [165](#)
- [l4\\_debugger\\_query\\_log\\_typeid](#)
  - Kernel Debugger, [166](#)
- [l4\\_debugger\\_query\\_obj\\_infos](#)
  - obj\_info.h, [3217](#)
- [l4\\_debugger\\_query\\_object\\_name](#)
  - Kernel Debugger, [167](#)
- [l4\\_debugger\\_set\\_object\\_name](#)
  - Kernel Debugger, [168](#)
- [l4\\_debugger\\_switch\\_log](#)
  - Kernel Debugger, [168](#)
- [L4\\_DEBUGGER\\_TASK\\_ADD\\_IMAGE\\_INFO\\_OP](#)
  - debugger.h, [3136](#)
- [l4\\_default\\_caps\\_t](#)
  - Capabilities, [439](#)
- [L4\\_DISABLE\\_COPY](#)
  - capability, [3047](#)
- [L4\\_E2BIG](#)
  - Error codes, [206](#)
- [L4\\_EACCESS](#)
  - Error codes, [206](#)
- [L4\\_EADDRNOTAVAIL](#)
  - Error codes, [206](#)
- [L4\\_EAGAIN](#)
  - Error codes, [206](#)
- [L4\\_EBADPROTO](#)
  - Error codes, [206](#)
- [L4\\_EBUSY](#)
  - Error codes, [206](#)
- [L4\\_EEXIST](#)
  - Error codes, [206](#)
- [L4\\_EFAULT](#)
  - Error codes, [206](#)
- [L4\\_EINVAL](#)
  - Error codes, [206](#)
- [L4\\_EIO](#)
  - Error codes, [206](#)
- [L4\\_EIPC\\_HI](#)
  - Error codes, [207](#)
- [L4\\_EIPC\\_LO](#)
  - Error codes, [207](#)



- L4\_MSGERRRANGE
  - Error codes, [207](#)
- L4\_MSGMISSARG
  - Error codes, [207](#)
- L4\_MSGTOO LONG
  - Error codes, [207](#)
- L4\_MSGTOO SHORT
  - Error codes, [206](#)
- L4\_ENAMETOOLONG
  - Error codes, [206](#)
- L4\_ENODEV
  - Error codes, [206](#)
- L4\_ENOENT
  - Error codes, [206](#)
- L4\_ENOMEM
  - Error codes, [206](#)
- L4\_ENOREPLY
  - Error codes, [206](#)
- L4\_ENOSPC
  - Error codes, [206](#)
- L4\_ENOSYS
  - Error codes, [206](#)
- L4\_ENOTDIR
  - Error codes, [206](#)
- L4\_ENXIO
  - Error codes, [206](#)
- L4\_EOK
  - Error codes, [206](#)
- L4\_EPERM
  - Error codes, [206](#)
- L4\_ERANGE
  - Error codes, [206](#)
- L4\_ERRNOMAX
  - Error codes, [206](#)
- l4\_error
  - Error Handling, [243](#)
- l4\_error\_code\_t
  - Error codes, [206](#)
- l4\_exc\_regs\_t, [1528](#)
  - flags, [1530](#)
  - ss, [1530](#)
- L4\_EXPORT
  - Basic Macros, [154](#)
- l4\_factory\_create
  - Factory, [284](#)
- l4\_factory\_create\_factory
  - Factory, [284](#)
- l4\_factory\_create\_gate
  - Factory, [285](#)
- l4\_factory\_create\_irq
  - Factory, [286](#)
- l4\_factory\_create\_task
  - Factory, [287](#)
- l4\_factory\_create\_thread
  - Factory, [288](#)
- l4\_factory\_create\_thread\_group
  - Factory, [289](#)
- l4\_factory\_create\_vcpu\_context
  - Factory, [290](#)
- l4\_factory\_create\_vm
  - Factory, [291](#)
- L4\_FP\_ALL\_SPACES
  - Task, [364](#)
- L4\_FP\_DELETE\_OBJ
  - Task, [364](#)
- L4\_FP\_OTHER\_SPACES
  - Task, [364](#)
- l4\_fpage
  - Flexpages, [179](#)
- L4\_FPAGE\_ADDR\_BITS
  - Flexpages, [178](#)
- L4\_FPAGE\_ADDR\_SHIFT
  - Flexpages, [178](#)
- l4\_fpage\_all
  - Flexpages, [180](#)
- L4\_FPAGE\_BUFFERABLE
  - Message Items, [227](#)
- L4\_FPAGE\_C\_IPCGATE\_SVR
  - Attributes and additional permissions for object send items, [232](#)
- L4\_FPAGE\_CACHE\_OPT
  - Message Items, [227](#)
- l4\_fpage\_cacheability\_opt\_t
  - Message Items, [227](#)
- L4\_FPAGE\_CACHEABLE
  - Message Items, [227](#)
- L4\_fpage\_consts
  - Flexpages, [177](#)
- l4\_fpage\_contains
  - Flexpages, [180](#)
- L4\_fpage\_control
  - Flexpages, [178](#)
- L4\_FPAGE\_CONTROL\_MASK
  - Flexpages, [178](#)
- L4\_FPAGE\_CONTROL\_OFFSET\_SHIFT
  - Flexpages, [178](#)
- l4\_fpage\_invalid
  - Flexpages, [181](#)
- L4\_FPAGE\_IO
  - Flexpages, [179](#)
- l4\_fpage\_ioport
  - Flexpages, [181](#)
- l4\_fpage\_max\_order
  - Flexpages, [182](#)
- l4\_fpage\_memaddr
  - Flexpages, [183](#)
- L4\_FPAGE\_MEMORY
  - Flexpages, [179](#)
- L4\_FPAGE\_OBJ
  - Flexpages, [179](#)
- l4\_fpage\_obj
  - Flexpages, [183](#)
- l4\_fpage\_page
  - Flexpages, [184](#)
- L4\_fpage\_rights
  - Flexpages, [178](#)



- l4\_fpage\_rights
  - Flexpages, [184](#)
- L4\_FPAGE\_RIGHTS\_ALL
  - Flexpages, [178](#)
- L4\_FPAGE\_RIGHTS\_BITS
  - Flexpages, [178](#)
- L4\_FPAGE\_RIGHTS\_MASK
  - Flexpages, [178](#)
- L4\_FPAGE\_RIGHTS\_SHIFT
  - Flexpages, [177](#)
- L4\_FPAGE\_RO
  - Flexpages, [178](#)
- L4\_FPAGE\_RW
  - Flexpages, [178](#)
- L4\_FPAGE\_RWX
  - Flexpages, [179](#)
- L4\_FPAGE\_RX
  - Flexpages, [179](#)
- l4\_fpage\_set\_rights
  - Flexpages, [185](#)
- l4\_fpage\_size
  - Flexpages, [186](#)
- L4\_FPAGE\_SIZE\_BITS
  - Flexpages, [178](#)
- L4\_FPAGE\_SIZE\_SHIFT
  - Flexpages, [178](#)
- L4\_FPAGE\_SPECIAL
  - Flexpages, [179](#)
- l4\_fpage\_t, [1531](#)
- L4\_fpage\_type
  - Flexpages, [179](#)
- l4\_fpage\_type
  - Flexpages, [187](#)
- L4\_FPAGE\_TYPE\_BITS
  - Flexpages, [178](#)
- L4\_FPAGE\_TYPE\_SHIFT
  - Flexpages, [177](#)
- L4\_FPAGE\_UNCACHEABLE
  - Message Items, [227](#)
- L4\_FPAGE\_W
  - Flexpages, [178](#)
- L4\_FPAGE\_X
  - Flexpages, [178](#)
- l4\_get\_hz
  - Timestamp Counter, [654](#)
- L4\_HIDDEN
  - Basic Macros, [154](#)
- l4\_icu\_bind
  - Interrupt controller, [317](#)
- l4\_icu\_bind\_u
  - Interrupt controller, [318](#)
- L4\_ICU\_FLAG\_MSI
  - Interrupt controller, [317](#)
- L4\_icu\_flags
  - Interrupt controller, [317](#)
- l4\_icu\_info
  - Interrupt controller, [319](#)
- l4\_icu\_info\_t, [1532](#)
  - features, [1533](#)
  - Interrupt controller, [316](#)
- l4\_icu\_info\_u
  - Interrupt controller, [320](#)
- l4\_icu\_mask
  - Interrupt controller, [321](#)
- l4\_icu\_mask\_u
  - Interrupt controller, [322](#)
- l4\_icu\_msi\_info
  - Interrupt controller, [323](#)
- l4\_icu\_msi\_info\_t, [1533](#)
- l4\_icu\_msi\_info\_u
  - Interrupt controller, [324](#)
- L4\_ICU\_OP\_BIND
  - L4 IPC Opcodes, [472](#)
- L4\_ICU\_OP\_INFO
  - L4 IPC Opcodes, [472](#)
- L4\_ICU\_OP\_MASK
  - L4 IPC Opcodes, [472](#)
- L4\_ICU\_OP\_MSI\_INFO
  - L4 IPC Opcodes, [472](#)
- L4\_ICU\_OP\_SET\_MODE
  - L4 IPC Opcodes, [472](#)
- L4\_ICU\_OP\_UNBIND
  - L4 IPC Opcodes, [472](#)
- L4\_ICU\_OP\_UNMASK
  - L4 IPC Opcodes, [472](#)
- L4\_icu\_opcode
  - L4 IPC Opcodes, [471](#)
- l4\_icu\_set\_mode
  - Interrupt controller, [325](#)
- l4\_icu\_set\_mode\_u
  - Interrupt controller, [326](#)
- l4\_icu\_unbind
  - Interrupt controller, [327](#)
- l4\_icu\_unbind\_u
  - Interrupt controller, [328](#)
- l4\_icu\_unmask
  - Interrupt controller, [329](#)
- l4\_icu\_unmask\_u
  - Interrupt controller, [330](#)
- l4\_infinite\_loop
  - Basic Macros, [157](#)
- L4\_INLINE\_RPC
  - ipc\_iface, [3086](#)
- L4\_INLINE\_RPC\_NF
  - ipc\_iface, [3086](#)
- L4\_INLINE\_RPC\_NF\_OP
  - ipc\_iface, [3086](#)
- L4\_INLINE\_RPC\_OP
  - ipc\_iface, [3087](#)
- L4\_INVALID\_ADDR
  - Memory related, [201](#)
- l4\_iofpage
  - Flexpages, [187](#)
- L4\_IOPORT\_MAX
  - Flexpages, [176](#)
- l4\_ipc

- Object Invocation, [210](#)
- l4\_ipc\_call
  - Object Invocation, [211](#)
- L4\_IPC\_ENOT\_EXISTENT
  - Error Handling, [242](#)
- l4\_ipc\_error
  - Error Handling, [244](#)
- l4\_ipc\_error\_code
  - Error Handling, [245](#)
- L4\_IPC\_ERROR\_MASK
  - Error Handling, [242](#)
- L4\_IPC\_GATE\_BIND\_OP
  - L4 IPC Opcodes, [472](#)
- L4\_IPC\_GATE\_GET\_INFO\_OP
  - L4 IPC Opcodes, [472](#)
- l4\_ipc\_gate\_get\_infos
  - IPC-Gate API, [276](#)
- L4\_ipc\_gate\_ops
  - L4 IPC Opcodes, [472](#)
- l4\_ipc\_is\_rcv\_error
  - Error Handling, [246](#)
- l4\_ipc\_is\_snd\_error
  - Error Handling, [246](#)
- L4\_IPC\_REABORTED
  - Error Handling, [243](#)
- L4\_IPC\_RECANCELED
  - Error Handling, [242](#)
- l4\_ipc\_receive
  - Object Invocation, [214](#)
- L4\_IPC\_REMAPFAILED
  - Error Handling, [242](#)
- L4\_IPC\_REMSGCUT
  - Error Handling, [243](#)
- l4\_ipc\_reply\_and\_wait
  - Object Invocation, [216](#)
- L4\_IPC\_RERCVPFTO
  - Error Handling, [242](#)
- L4\_IPC\_RESNDPFTO
  - Error Handling, [242](#)
- L4\_IPC\_RETIMEOUT
  - Error Handling, [242](#)
- L4\_IPC\_SEABORTED
  - Error Handling, [243](#)
- L4\_IPC\_SECANCELED
  - Error Handling, [242](#)
- L4\_IPC\_SEMAPFAILED
  - Error Handling, [242](#)
- L4\_IPC\_SEMSGCUT
  - Error Handling, [243](#)
- l4\_ipc\_send
  - Object Invocation, [217](#)
- l4\_ipc\_send\_and\_wait
  - Object Invocation, [219](#)
- L4\_IPC\_SERCVPFTO
  - Error Handling, [243](#)
- L4\_IPC\_SESNDPFTO
  - Error Handling, [242](#)
- L4\_IPC\_SETIMEOUT
  - Error Handling, [242](#)
- l4\_ipc\_sleep
  - Object Invocation, [220](#)
- l4\_ipc\_sleep\_ms
  - Object Invocation, [221](#)
- l4\_ipc\_sleep\_us
  - Object Invocation, [222](#)
- L4\_IPC\_SND\_ERR\_MASK
  - Error Handling, [242](#)
- l4\_ipc\_tcr\_error\_t
  - Error Handling, [242](#)
- l4\_ipc\_timeout
  - Timeouts, [235](#)
- L4\_IPC\_TIMEOUT\_0
  - Timeouts, [234](#)
- l4\_ipc\_to\_errno
  - ipc.h, [3165](#)
- l4\_ipc\_wait
  - Object Invocation, [223](#)
- l4\_irq\_bind\_vcpu
  - IRQs, [333](#)
- l4\_irq\_bind\_vcpu\_u
  - IRQs, [334](#)
- l4\_irq\_detach
  - IRQs, [336](#)
- l4\_irq\_detach\_u
  - IRQs, [337](#)
- L4\_IRQ\_F\_BOTH
  - IRQs, [333](#)
- L4\_IRQ\_F\_BOTH\_EDGE
  - IRQs, [333](#)
- L4\_IRQ\_F\_CLEAR\_WAKEUP
  - IRQs, [333](#)
- L4\_IRQ\_F\_EDGE
  - IRQs, [333](#)
- L4\_IRQ\_F\_LEVEL
  - IRQs, [333](#)
- L4\_IRQ\_F\_LEVEL\_HIGH
  - IRQs, [333](#)
- L4\_IRQ\_F\_LEVEL\_LOW
  - IRQs, [333](#)
- L4\_IRQ\_F\_MASK
  - IRQs, [333](#)
- L4\_IRQ\_F\_NEG
  - IRQs, [333](#)
- L4\_IRQ\_F\_NEG\_EDGE
  - IRQs, [333](#)
- L4\_IRQ\_F\_NONE
  - IRQs, [333](#)
- L4\_IRQ\_F\_POS
  - IRQs, [333](#)
- L4\_IRQ\_F\_POS\_EDGE
  - IRQs, [333](#)
- L4\_IRQ\_F\_SET\_MODE
  - IRQs, [333](#)
- L4\_IRQ\_F\_SET\_WAKEUP
  - IRQs, [333](#)
- L4\_irq\_mode

- IRQs, [333](#)
- `l4_irq_receive`
  - IRQs, [338](#)
- `l4_irq_receive_u`
  - IRQs, [339](#)
- `l4_irq_trigger`
  - IRQs, [340](#)
- `l4_irq_trigger_u`
  - IRQs, [341](#)
- `l4_irq_unmask`
  - IRQs, [342](#)
- `l4_irq_unmask_u`
  - IRQs, [343](#)
- `l4_irq_wait`
  - IRQs, [344](#)
- `l4_irq_wait_u`
  - IRQs, [345](#)
- `l4_is_fpage_valid`
  - Flexpages, [188](#)
- `l4_is_fpage_writable`
  - Flexpages, [189](#)
- `l4_is_invalid_cap`
  - Capabilities, [440](#)
- `l4_is_valid_cap`
  - Capabilities, [440](#)
- `L4_ITEM_CONT`
  - Message Items, [227](#)
- `L4_ITEM_MAP`
  - Message Items, [227](#)
- `l4_kd_enter`
  - `kdebug.h`, [3186](#)
- `l4_kd_outchar`
  - `kdebug.h`, [3187](#)
- `l4_kd_outdec`
  - `kdebug.h`, [3188](#)
- `l4_kd_outhex12`
  - `kdebug.h`, [3188](#)
- `l4_kd_outhex16`
  - `kdebug.h`, [3189](#)
- `l4_kd_outhex20`
  - `kdebug.h`, [3189](#)
- `l4_kd_outhex32`
  - `kdebug.h`, [3190](#)
- `l4_kd_outhex64`
  - `kdebug.h`, [3190](#)
- `l4_kd_outhex8`
  - `kdebug.h`, [3191](#)
- `l4_kd_outnstring`
  - `kdebug.h`, [3192](#)
- `l4_kd_outstring`
  - `kdebug.h`, [3193](#)
- `l4_kd_outumword`
  - `kdebug.h`, [3193](#)
- `l4_kdebug_ops_t`
  - `kdebug.h`, [3181](#)
- `l4_kernel_info_get_mem_desc_end`
  - Memory descriptors (C version), [435](#)
- `l4_kernel_info_get_mem_desc_is_virtual`
  - Memory descriptors (C version), [435](#)
- `l4_kernel_info_get_mem_desc_start`
  - Memory descriptors (C version), [435](#)
- `l4_kernel_info_get_mem_desc_subtype`
  - Memory descriptors (C version), [435](#)
- `l4_kernel_info_get_mem_desc_type`
  - Memory descriptors (C version), [436](#)
- `l4_kernel_info_get_num_mem_descs`
  - Memory descriptors (C version), [436](#)
- `l4_kernel_info_mem_desc_t`, [1534](#)
  - Memory descriptors (C version), [433](#)
- `l4_kernel_info_set_mem_desc`
  - Memory descriptors (C version), [436](#)
- `l4_kernel_info_t`, [1535](#)
  - Kernel Interface Page, [427](#)
- `l4_kernel_info_version_offset`
  - Kernel Interface Page, [428](#)
- `l4_kip`
  - Kernel Interface Page, [428](#)
- `l4_kip_clock`
  - Kernel Interface Page, [428](#)
- `l4_kip_clock_lw`
  - Kernel Interface Page, [429](#)
- `l4_kip_clock_ns`
  - Kernel Interface Page, [430](#)
- `l4_kip_for_each_feature`
  - `kip.h`, [3345](#)
- `l4_kip_kernel_has_feature`
  - `kip.h`, [3345](#)
- `L4_KIP_OFFS_READ_NS`
  - Kernel Interface Page, [427](#)
- `L4_KIP_OFFS_READ_US`
  - Kernel Interface Page, [427](#)
- `l4_kip_version`
  - Kernel Interface Page, [430](#)
- `l4_kip_version_string`
  - Kernel Interface Page, [431](#)
- `L4_LOG2_PAGESIZE`
  - Memory related, [198](#)
- `L4_LOG2_SUPERPAGESIZE`
  - Memory related, [198](#)
- `l4_map_control`
  - Message Items, [229](#)
- `L4_MAP_ITEM_GRANT`
  - Message Items, [228](#)
- `L4_MAP_ITEM_MAP`
  - Message Items, [228](#)
- `l4_map_obj_control`
  - Message Items, [230](#)
- `l4_mem_archspecific_acpi_nvs`
  - Memory descriptors (C version), [434](#)
- `l4_mem_archspecific_acpi_tables`
  - Memory descriptors (C version), [434](#)
- `l4_mem_archspecific_sub_type_common_t`
  - Memory descriptors (C version), [434](#)
- `l4_mem_info_acpi_rsdp`
  - Memory descriptors (C version), [434](#)
- `l4_mem_info_sub_type_t`

- Memory descriptors (C version), [434](#)
- L4\_mem\_op\_widths
  - Memory Operations, [442](#)
- l4\_mem\_read
  - Memory Operations, [443](#)
- l4\_mem\_reserved\_heap
  - Memory descriptors (C version), [434](#)
- l4\_mem\_reserved\_kernel
  - Memory descriptors (C version), [434](#)
- l4\_mem\_reserved\_mmio
  - Memory descriptors (C version), [434](#)
- l4\_mem\_type\_archspecific
  - Memory descriptors (C version), [435](#)
- l4\_mem\_type\_bootloader
  - Memory descriptors (C version), [434](#)
- l4\_mem\_type\_conventional
  - Memory descriptors (C version), [434](#)
- l4\_mem\_type\_dedicated
  - Memory descriptors (C version), [434](#)
- l4\_mem\_type\_info
  - Memory descriptors (C version), [434](#)
- l4\_mem\_type\_reserved
  - Memory descriptors (C version), [434](#)
- l4\_mem\_type\_shared
  - Memory descriptors (C version), [434](#)
- l4\_mem\_type\_t
  - Memory descriptors (C version), [434](#)
- l4\_mem\_type\_undefined
  - Memory descriptors (C version), [434](#)
- L4\_MEM\_WIDTH\_1BYTE
  - Memory Operations, [442](#)
- L4\_MEM\_WIDTH\_2BYTE
  - Memory Operations, [442](#)
- L4\_MEM\_WIDTH\_4BYTE
  - Memory Operations, [442](#)
- l4\_mem\_write
  - Memory Operations, [443](#)
- l4\_msg\_item\_consts\_t
  - Message Items, [227](#)
- l4\_msg\_regs\_t, [1536](#)
- l4\_msgtag
  - Message Tag, [250](#)
- L4\_MSGTAG\_ERROR
  - Message Tag, [249](#)
- L4\_MSGTAG\_FLAGS
  - Message Tag, [249](#)
- L4\_msgtag\_flags
  - Message Tag, [249](#)
- l4\_msgtag\_flags
  - Message Tag, [252](#)
- l4\_msgtag\_has\_error
  - Message Tag, [253](#)
- l4\_msgtag\_is\_exception
  - Message Tag, [254](#)
- l4\_msgtag\_is\_io\_page\_fault
  - Message Tag, [255](#)
- l4\_msgtag\_is\_page\_fault
  - Message Tag, [256](#)
- l4\_msgtag\_is\_sigma0
  - Message Tag, [257](#)
- l4\_msgtag\_items
  - Message Tag, [257](#)
- l4\_msgtag\_label
  - Message Tag, [258](#)
- L4\_msgtag\_protocol
  - Message Tag, [249](#)
- L4\_MSGTAG\_SCHEDULE
  - Message Tag, [249](#)
- l4\_msgtag\_t, [1537](#)
  - flags, [1539](#)
  - has\_error, [1539](#)
- L4\_MSGTAG\_TRANSFER\_FPU
  - Message Tag, [249](#)
- l4\_msgtag\_words
  - Message Tag, [259](#)
- L4\_NOTHROW
  - Basic Macros, [155](#)
- l4\_ns\_to\_tsc
  - Timestamp Counter, [654](#)
- l4\_obj\_fpage
  - Flexpages, [190](#)
- L4\_PAGEMASK
  - Memory related, [198](#)
- L4\_PAGESHIFT
  - Memory related, [198](#), [199](#)
- l4\_platform\_ctl\_cpu\_allow\_shutdown
  - Platform Control C API, [347](#)
- L4\_PLATFORM\_CTL\_CPU\_ALLOW\_SHUTDOWN\_OP
  - L4 IPC Opcodes, [473](#)
- l4\_platform\_ctl\_cpu\_disable
  - Platform Control C API, [348](#)
- L4\_PLATFORM\_CTL\_CPU\_DISABLE\_OP
  - L4 IPC Opcodes, [473](#)
- l4\_platform\_ctl\_cpu\_enable
  - Platform Control C API, [348](#)
- L4\_PLATFORM\_CTL\_CPU\_ENABLE\_OP
  - L4 IPC Opcodes, [473](#)
- l4\_platform\_ctl\_ops
  - L4 IPC Opcodes, [472](#)
- l4\_platform\_ctl\_proto
  - Message Tag, [250](#)
- l4\_platform\_ctl\_set\_task\_asid
  - Platform Control C API, [349](#)
- L4\_PLATFORM\_CTL\_SET\_TASK\_ASID\_OP
  - L4 IPC Opcodes, [473](#)
- L4\_PLATFORM\_CTL\_SYS\_SHUTDOWN\_OP
  - L4 IPC Opcodes, [473](#)
- L4\_PLATFORM\_CTL\_SYS\_SUSPEND\_OP
  - L4 IPC Opcodes, [473](#)
- l4\_platform\_ctl\_system\_shutdown
  - Platform Control C API, [350](#)
- l4\_platform\_ctl\_system\_suspend
  - Platform Control C API, [351](#)
- L4\_PROTO\_ALLOW\_SYSCALL
  - Message Tag, [249](#)
- L4\_PROTO\_DEBUGGER

- Message Tag, [250](#)
- L4\_PROTO\_DMA\_SPACE
  - Message Tag, [250](#)
- L4\_PROTO\_EXCEPTION
  - Message Tag, [250](#)
- L4\_PROTO\_FACTORY
  - Message Tag, [250](#)
- L4\_PROTO\_IO\_PAGE\_FAULT
  - Message Tag, [250](#)
- L4\_PROTO\_IOMMU
  - Message Tag, [250](#)
- L4\_PROTO\_IRQ
  - Message Tag, [249](#)
- L4\_PROTO\_IRQ\_SENDER
  - Message Tag, [250](#)
- L4\_PROTO\_KOBJECT
  - Message Tag, [250](#)
- L4\_PROTO\_LOG
  - Message Tag, [250](#)
- L4\_PROTO\_META
  - Message Tag, [250](#)
- L4\_PROTO\_NONE
  - Message Tag, [249](#)
- L4\_PROTO\_PAGE\_FAULT
  - Message Tag, [249](#)
- L4\_PROTO\_PF\_EXCEPTION
  - Message Tag, [249](#)
- L4\_PROTO\_PLATFORM\_CTL
  - Message Tag, [250](#)
- L4\_PROTO\_SCHEDULER
  - Message Tag, [250](#)
- L4\_PROTO\_SEMAPHORE
  - Message Tag, [250](#)
- L4\_PROTO\_SIGMA0
  - Message Tag, [250](#)
- L4\_PROTO\_SMCCC
  - Message Tag, [250](#)
- l4\_proto\_t
  - types.h, [3270](#)
- L4\_PROTO\_TASK
  - Message Tag, [250](#)
- L4\_PROTO\_THREAD
  - Message Tag, [250](#)
- L4\_PROTO\_THREAD\_GROUP
  - Message Tag, [250](#)
- L4\_PROTO\_VCPU\_CONTEXT
  - Message Tag, [250](#)
- L4\_PROTO\_VM
  - Message Tag, [250](#)
- L4\_RCV\_EP\_BIND\_OP
  - rcv\_endpoint.h, [3231](#)
- l4\_rcv\_ep\_bind\_snd\_destination
  - IPC-Gate API, [277](#)
- l4\_rcv\_ep\_bind\_thread
  - IPC-Gate API, [278](#)
- L4\_rcv\_ep\_ops
  - rcv\_endpoint.h, [3231](#)
- L4\_RCV\_ITEM\_FORWARD\_MAPPINGS
  - Message Items, [228](#)
- L4\_RCV\_ITEM\_LOCAL\_ID
  - Message Items, [229](#)
- L4\_RCV\_ITEM\_SINGLE\_CAP
  - Message Items, [228](#)
- l4\_rcv\_timeout
  - Timeouts, [235](#)
- l4\_rdpmc
  - Timestamp Counter, [655](#)
- l4\_rdpmc\_32
  - Timestamp Counter, [655](#)
- l4\_rdtsc
  - Timestamp Counter, [656](#)
- l4\_rdtsc\_32
  - Timestamp Counter, [656](#)
- l4\_ret\_t
  - types.h, [3270](#)
- l4\_round\_page
  - Memory related, [201](#)
- l4\_round\_size
  - Memory related, [202](#)
- L4\_RPC
  - ipc\_iface, [3087](#)
- L4\_RPC\_DEF
  - ipc\_client, [3078](#)
- L4\_RPC\_NF
  - ipc\_iface, [3088](#)
- L4\_RPC\_NF\_OP
  - ipc\_iface, [3088](#)
- L4\_RPC\_OP
  - ipc\_iface, [3089](#)
- l4\_sched\_cpu\_set
  - Scheduler, [354](#)
- l4\_sched\_cpu\_set\_t, [1540](#)
  - gran\_offset, [1543](#)
  - granularity, [1541](#)
  - offset, [1541](#)
  - set, [1542](#)
- l4\_sched\_param
  - Scheduler, [355](#)
- l4\_sched\_param\_t, [1544](#)
  - prio, [1545](#)
- L4\_SCHEDULER\_CLASS\_FIXED\_PRIO
  - Scheduler, [354](#)
- L4\_SCHEDULER\_CLASS\_WFQ
  - Scheduler, [354](#)
- L4\_scheduler\_classes
  - Scheduler, [354](#)
- l4\_scheduler\_idle\_time
  - Scheduler, [356](#)
- L4\_SCHEDULER\_IDLE\_TIME\_OP
  - Scheduler, [354](#)
- l4\_scheduler\_info
  - Scheduler, [357](#)
- L4\_SCHEDULER\_INFO\_OP
  - Scheduler, [354](#)
- l4\_scheduler\_info\_with\_classes
  - Scheduler, [357](#)

- l4\_scheduler\_is\_online
  - Scheduler, [358](#)
- L4\_scheduler\_ops
  - Scheduler, [354](#)
- l4\_scheduler\_run\_thread
  - Scheduler, [359](#)
- L4\_SCHEDULER\_RUN\_THREAD\_OP
  - Scheduler, [354](#)
- l4\_semaphore\_down
  - Kernel-provided semaphore, [361](#)
- l4\_semaphore\_up
  - Kernel-provided semaphore, [361](#)
- l4\_sleep
  - Utility Functions, [638](#)
- l4\_snd\_fpage\_t, [1545](#)
- l4\_snd\_timeout
  - Timeouts, [235](#)
- l4\_sndfpage\_add
  - Object Invocation, [224](#)
- L4\_SUPERPAGEMASK
  - Memory related, [199](#)
- L4\_SUPERPAGESHIFT
  - Memory related, [199](#), [200](#)
- L4\_SUPERPAGESIZE
  - Memory related, [200](#)
- L4\_sys\_segment
  - segment.h, [2449](#)
- L4\_SYSF\_CALL
  - consts.h, [3060](#)
- L4\_SYSF\_NONE
  - Object Invocation, [209](#)
- L4\_SYSF\_OPEN\_WAIT
  - consts.h, [3061](#)
- L4\_SYSF\_RECV
  - consts.h, [3061](#)
- L4\_SYSF\_REPLY
  - consts.h, [3061](#)
- L4\_SYSF\_REPLY\_AND\_WAIT
  - consts.h, [3061](#)
- L4\_SYSF\_SEND
  - consts.h, [3062](#)
- L4\_SYSF\_SEND\_AND\_WAIT
  - consts.h, [3062](#)
- L4\_SYSF\_WAIT
  - consts.h, [3062](#)
- l4\_task\_add\_ku\_mem
  - Task, [364](#)
- L4\_TASK\_ADD\_KU\_MEM\_OP
  - L4 IPC Opcodes, [473](#)
- l4\_task\_cap\_equal
  - Task, [365](#)
- L4\_TASK\_CAP\_INFO\_OP
  - L4 IPC Opcodes, [473](#)
- l4\_task\_cap\_valid
  - Task, [366](#)
- l4\_task\_delete\_obj
  - Task, [367](#)
- L4\_TASK\_LDT\_SET\_X86\_OP
  - L4 IPC Opcodes, [473](#)
- L4\_task\_ldt\_x86\_consts
  - segment.h, [2449](#), [2455](#)
- L4\_TASK\_LDT\_X86\_ENTRY\_SIZE
  - segment.h, [2449](#), [2455](#)
- L4\_TASK\_LDT\_X86\_MAX\_ENTRIES
  - segment.h, [2449](#), [2455](#)
- l4\_task\_map
  - Task, [368](#)
- L4\_TASK\_MAP\_OP
  - L4 IPC Opcodes, [473](#)
- L4\_TASK\_MAP\_VGICC\_ARM\_OP
  - L4 IPC Opcodes, [473](#)
- L4\_task\_ops
  - L4 IPC Opcodes, [473](#)
- l4\_task\_release\_cap
  - Task, [370](#)
- l4\_task\_unmap
  - Task, [370](#)
- l4\_task\_unmap\_batch
  - Task, [372](#)
- L4\_TASK\_UNMAP\_OP
  - L4 IPC Opcodes, [473](#)
- l4\_task\_vgicc\_map
  - Task, [373](#)
- L4\_THREAD\_AMD64\_GET\_SEGMENT\_INFO\_OP
  - L4 IPC Opcodes, [474](#)
- L4\_THREAD\_AMD64\_SET\_SEGMENT\_BASE\_OP
  - L4 IPC Opcodes, [474](#)
- l4\_thread\_arm\_set\_tpidruro
  - Thread, [379](#)
- L4\_THREAD\_ARM\_TPIDRURO\_OP
  - L4 IPC Opcodes, [474](#)
- L4\_THREAD\_CONTROL\_ALIEN
  - Thread, [377](#)
- l4\_thread\_control\_alien
  - Thread control, [398](#)
- l4\_thread\_control\_bind
  - Thread control, [399](#)
- L4\_THREAD\_CONTROL\_BIND\_TASK
  - Thread, [377](#)
- l4\_thread\_control\_commit
  - Thread control, [400](#)
- l4\_thread\_control\_exc\_handler
  - Thread control, [401](#)
- L4\_thread\_control\_flags
  - Thread, [377](#)
- L4\_THREAD\_CONTROL\_MR\_IDX\_BIND\_TASK
  - Thread, [377](#)
- L4\_THREAD\_CONTROL\_MR\_IDX\_BIND\_UTCB
  - Thread, [377](#)
- L4\_THREAD\_CONTROL\_MR\_IDX\_EXC\_HANDLER
  - Thread, [377](#)
- L4\_THREAD\_CONTROL\_MR\_IDX\_FLAG\_VALS
  - Thread, [377](#)
- L4\_THREAD\_CONTROL\_MR\_IDX\_FLAGS
  - Thread, [377](#)
- L4\_THREAD\_CONTROL\_MR\_IDX\_PAGER

- Thread, [377](#)
- L4\_thread\_control\_mr\_indices
  - Thread, [377](#)
- L4\_THREAD\_CONTROL\_OP
  - L4 IPC Opcodes, [473](#)
- l4\_thread\_control\_pager
  - Thread control, [401](#)
- L4\_THREAD\_CONTROL\_SET\_EXC\_HANDLER
  - Thread, [377](#)
- L4\_THREAD\_CONTROL\_SET\_PAGER
  - Thread, [377](#)
- l4\_thread\_control\_start
  - Thread control, [402](#)
- l4\_thread\_ex\_regs
  - Thread, [379](#)
- L4\_THREAD\_EX\_REGS\_ARCH\_MASK
  - Thread, [378](#)
- L4\_THREAD\_EX\_REGS\_ARM64\_SET\_EL\_EL0
  - Thread, [378](#)
- L4\_THREAD\_EX\_REGS\_ARM64\_SET\_EL\_EL1
  - Thread, [378](#)
- L4\_THREAD\_EX\_REGS\_ARM64\_SET\_EL\_KEEP
  - Thread, [378](#)
- L4\_THREAD\_EX\_REGS\_ARM64\_SET\_EL\_MASK
  - Thread, [378](#)
- L4\_THREAD\_EX\_REGS\_ARM\_SET\_EL\_EL0
  - Thread, [378](#)
- L4\_THREAD\_EX\_REGS\_ARM\_SET\_EL\_EL1
  - Thread, [378](#)
- L4\_THREAD\_EX\_REGS\_ARM\_SET\_EL\_KEEP
  - Thread, [378](#)
- L4\_THREAD\_EX\_REGS\_ARM\_SET\_EL\_MASK
  - Thread, [378](#)
- L4\_THREAD\_EX\_REGS\_CANCEL
  - Thread, [378](#)
- L4\_thread\_ex\_regs\_flags
  - Thread, [377](#)
- L4\_thread\_ex\_regs\_flags\_arm
  - Thread, [378](#)
- L4\_thread\_ex\_regs\_flags\_arm64
  - Thread, [378](#)
- L4\_THREAD\_EX\_REGS\_OP
  - L4 IPC Opcodes, [474](#)
- l4\_thread\_ex\_regs\_ret
  - Thread, [380](#)
- l4\_thread\_ex\_regs\_ret\_u
  - Thread, [381](#)
- L4\_THREAD\_EX\_REGS\_TRIGGER\_EXCEPTION
  - Thread, [378](#)
- l4\_thread\_ex\_regs\_u
  - Thread, [382](#)
- l4\_thread\_group\_add
  - Thread groups, [409](#)
- l4\_thread\_group\_remove
  - Thread groups, [409](#)
- l4\_thread\_modify\_sender\_add
  - Thread, [384](#)
- l4\_thread\_modify\_sender\_commit
  - Thread, [385](#)
- L4\_THREAD\_MODIFY\_SENDER\_OP
  - L4 IPC Opcodes, [474](#)
- l4\_thread\_modify\_sender\_start
  - Thread, [385](#)
- L4\_THREAD\_OPCODE\_MASK
  - L4 IPC Opcodes, [474](#)
- L4\_thread\_ops
  - L4 IPC Opcodes, [473](#)
- l4\_thread\_register\_del\_irq
  - Thread, [386](#)
- L4\_THREAD\_REGISTER\_DELETE\_IRQ\_OP
  - L4 IPC Opcodes, [474](#)
- l4\_thread\_register\_doorbell\_irq
  - Thread, [387](#)
- L4\_THREAD\_REGISTER\_DOORBELL\_IRQ\_OP
  - L4 IPC Opcodes, [474](#)
- l4\_thread\_regs\_t, [1546](#)
  - error, [1547](#)
  - free\_marker, [1547](#)
- L4\_THREAD\_STATS\_OP
  - L4 IPC Opcodes, [474](#)
- l4\_thread\_stats\_time
  - Thread, [388](#)
- l4\_thread\_switch
  - Thread, [389](#)
- L4\_THREAD\_SWITCH\_OP
  - L4 IPC Opcodes, [474](#)
- l4\_thread\_vcpu\_control
  - Thread, [390](#)
- l4\_thread\_vcpu\_control\_ext
  - Thread, [391](#)
- l4\_thread\_vcpu\_control\_ext\_u
  - Thread, [392](#)
- L4\_THREAD\_VCPU\_CONTROL\_OP
  - L4 IPC Opcodes, [474](#)
- l4\_thread\_vcpu\_control\_u
  - Thread, [393](#)
- l4\_thread\_vcpu\_resume\_commit
  - Thread, [394](#)
- L4\_THREAD\_VCPU\_RESUME\_OP
  - L4 IPC Opcodes, [474](#)
- l4\_thread\_vcpu\_resume\_start
  - Thread, [396](#)
- L4\_THREAD\_X86\_GDT\_OP
  - L4 IPC Opcodes, [474](#)
- l4\_thread\_yield
  - Thread, [396](#)
- l4\_timeout
  - Timeouts, [236](#)
- l4\_timeout\_abs
  - Timeouts, [236](#)
- l4\_timeout\_get
  - Timeouts, [237](#)
- l4\_timeout\_is\_absolute
  - Timeouts, [238](#)
- l4\_timeout\_rel
  - Timeouts, [239](#)

- l4\_timeout\_rel\_get
  - Timeouts, [239](#)
- l4\_timeout\_s, [1547](#)
  - Timeouts, [234](#)
- l4\_timeout\_t, [1548](#)
  - Timeouts, [234](#)
- L4\_TIMEOUT\_US\_MAX
  - Timeouts, [234](#)
- l4\_touch\_ro
  - Utility Functions, [638](#)
- l4\_touch\_rw
  - Utility Functions, [639](#)
- l4\_trunc\_page
  - Memory related, [203](#)
- l4\_trunc\_size
  - Memory related, [204](#)
- l4\_tsc\_init
  - Timestamp Counter, [656](#)
- l4\_tsc\_to\_ns
  - Timestamp Counter, [657](#)
- l4\_tsc\_to\_s\_and\_ns
  - Timestamp Counter, [657](#)
- l4\_tsc\_to\_us
  - Timestamp Counter, [658](#)
- l4\_unmap\_flags\_t
  - Task, [363](#)
- l4\_usleep
  - Utility Functions, [639](#)
- l4\_utcb\_br
  - Virtual Registers (UTCBs), [263](#)
- l4\_utcb\_exc
  - Exception registers, [266](#)
- l4\_utcb\_exc\_is\_ex\_regs\_exception
  - Exception registers, [267](#)
- l4\_utcb\_exc\_is\_pf
  - Exception registers, [267](#)
- l4\_utcb\_exc\_pc
  - Exception registers, [268](#)
- l4\_utcb\_exc\_pc\_set
  - Exception registers, [268](#)
- l4\_utcb\_mr
  - Virtual Registers (UTCBs), [263](#)
- l4\_utcb\_mr64\_idx
  - Timeouts, [240](#)
- l4\_utcb\_t
  - Virtual Registers (UTCBs), [262](#)
- l4\_utcb\_tcr
  - Virtual Registers (UTCBs), [264](#)
- l4\_vcon\_attr\_t, [1549](#)
  - set\_raw, [1550](#)
  - Virtual Console, [412](#)
- L4\_VCON\_ECHO
  - Virtual Console, [413](#)
- l4\_vcon\_get\_attr
  - Virtual Console, [414](#)
- L4\_VCON\_GET\_ATTR\_OP
  - L4 IPC Opcodes, [474](#)
- l4\_vcon\_get\_attr\_u
  - Virtual Console, [414](#)
- L4\_vcon\_i\_flags
  - Virtual Console, [413](#)
- L4\_VCON\_ICANON
  - Virtual Console, [413](#)
- L4\_VCON\_ICRNL
  - Virtual Console, [413](#)
- L4\_VCON\_IGNCR
  - Virtual Console, [413](#)
- L4\_VCON\_INLCR
  - Virtual Console, [413](#)
- L4\_vcon\_l\_flags
  - Virtual Console, [413](#)
- L4\_vcon\_o\_flags
  - Virtual Console, [413](#)
- L4\_VCON\_OCRNL
  - Virtual Console, [413](#)
- L4\_VCON\_ONLCR
  - Virtual Console, [413](#)
- L4\_VCON\_ONLRET
  - Virtual Console, [413](#)
- L4\_vcon\_ops
  - L4 IPC Opcodes, [474](#)
- l4\_vcon\_read
  - Virtual Console, [415](#)
- L4\_vcon\_read\_flags
  - vcon.h, [3292](#)
- L4\_VCON\_READ\_OP
  - L4 IPC Opcodes, [474](#)
- L4\_VCON\_READ\_SIZE
  - Virtual Console, [414](#)
- L4\_VCON\_READ\_SIZE\_MASK
  - vcon.h, [3292](#)
- L4\_VCON\_READ\_STAT\_BREAK
  - vcon.h, [3292](#)
- L4\_VCON\_READ\_STAT\_DONE
  - vcon.h, [3292](#)
- l4\_vcon\_read\_u
  - Virtual Console, [416](#)
- l4\_vcon\_read\_with\_flags
  - Virtual Console, [417](#)
- l4\_vcon\_send
  - Virtual Console, [418](#)
- l4\_vcon\_send\_u
  - Virtual Console, [419](#)
- l4\_vcon\_set\_attr
  - Virtual Console, [421](#)
- L4\_VCON\_SET\_ATTR\_OP
  - L4 IPC Opcodes, [474](#)
- l4\_vcon\_set\_attr\_raw
  - Virtual Console, [421](#)
- l4\_vcon\_set\_attr\_u
  - Virtual Console, [422](#)
- L4\_vcon\_size\_consts
  - Virtual Console, [413](#)
- l4\_vcon\_write
  - Virtual Console, [423](#)
- L4\_VCON\_WRITE\_OP



- L4 IPC Opcodes, [474](#)
- L4\_VCON\_WRITE\_SIZE
  - Virtual Console, [414](#)
- l4\_vcon\_write\_u
  - Virtual Console, [424](#)
- l4\_vcpu\_arch\_state\_t, [1551](#)
- l4\_vcpu\_check\_version
  - vcpu.h, [3395](#)
- L4\_vcpu\_e\_field\_ids
  - \_\_vcpu-arch.h, [2492](#), [2496](#)
- L4\_VCPU\_E\_VTMR\_CFG
  - \_\_vcpu-arch.h, [2493](#), [2496](#)
- L4\_VCPU\_F\_EXCEPTIONS
  - vCPU API, [406](#)
- L4\_VCPU\_F\_FPU\_ENABLED
  - vCPU API, [407](#)
- L4\_VCPU\_F\_IRQ
  - vCPU API, [406](#)
- L4\_VCPU\_F\_PAGE\_FAULTS
  - vCPU API, [406](#)
- L4\_VCPU\_F\_USER\_MODE
  - vCPU API, [406](#)
- l4\_vcpu\_ipc\_regs\_t, [1551](#)
- L4\_VCPU\_OFFSET\_EXT\_INFOS
  - vCPU API, [407](#), [408](#)
- L4\_VCPU\_OFFSET\_EXT\_STATE
  - vCPU API, [407](#), [408](#)
- l4\_vcpu\_regs\_t, [1553](#)
  - ax, [1555](#)
  - bp, [1555](#)
  - bx, [1555](#)
  - cx, [1555](#)
  - di, [1555](#)
  - dx, [1555](#)
  - si, [1556](#)
- L4\_VCPU\_SF\_IRQ\_PENDING
  - vCPU API, [408](#)
- L4\_vcpu\_state\_flags
  - vCPU API, [406](#)
- L4\_vcpu\_state\_offset
  - vCPU API, [407](#)
- l4\_vcpu\_state\_t, [1556](#)
  - version, [1559](#)
- L4\_VCPU\_STATE\_VERSION
  - \_\_vcpu-arch.h, [2490](#), [2492](#), [2496](#), [2499](#)
- L4\_vcpu\_sticky\_flags
  - vCPU API, [408](#)
- L4\_virtio\_cmd
  - L4 VIRTIO Transport Layer, [478](#)
- L4\_virtio\_irq\_status
  - L4 VIRTIO Transport Layer, [478](#)
- L4\_virtio\_opcodes
  - L4 VIRTIO Transport Layer, [478](#)
- l4\_vm\_svm\_vmcb\_control\_area, [1560](#)
- l4\_vm\_svm\_vmcb\_state\_save\_area, [1560](#)
- l4\_vm\_svm\_vmcb\_state\_save\_area\_seg, [1562](#)
- l4\_vm\_svm\_vmcb\_t, [1562](#)
- l4\_vm\_tz\_state, [1564](#)
- L4\_VM\_VMX\_BASIC\_REG
  - VM API for VMX, [299](#)
- L4\_vm\_vmx\_caps\_regs
  - VM API for VMX, [299](#)
- l4\_vm\_vmx\_clear
  - VM API for VMX, [301](#)
- L4\_VM\_VMX\_CR0\_FIXED0\_REG
  - VM API for VMX, [299](#)
- L4\_VM\_VMX\_CR0\_FIXED1\_REG
  - VM API for VMX, [299](#)
- L4\_VM\_VMX\_CR4\_FIXED0\_REG
  - VM API for VMX, [299](#)
- L4\_VM\_VMX\_CR4\_FIXED1\_REG
  - VM API for VMX, [299](#)
- L4\_vm\_vmx\_dfl1\_regs
  - VM API for VMX, [299](#)
- L4\_VM\_VMX\_ENTRY\_CTL5\_DFL1\_REG
  - VM API for VMX, [299](#)
- L4\_VM\_VMX\_EPT\_VPID\_CAP\_REG
  - VM API for VMX, [299](#)
- L4\_VM\_VMX\_EXIT\_CTL5\_DFL1\_REG
  - VM API for VMX, [299](#)
- l4\_vm\_vmx\_field\_len
  - VM API for VMX, [301](#)
- l4\_vm\_vmx\_field\_order
  - VM API for VMX, [302](#)
- l4\_vm\_vmx\_get\_caps
  - VM API for VMX, [303](#)
- l4\_vm\_vmx\_get\_caps\_default1
  - VM API for VMX, [303](#)
- l4\_vm\_vmx\_get\_cr2\_index
  - VM API for VMX, [304](#)
- l4\_vm\_vmx\_get\_hw\_vmcs
  - VM API for VMX, [304](#)
- L4\_VM\_VMX\_MISC\_REG
  - VM API for VMX, [299](#)
- L4\_VM\_VMX\_NESTED\_REVISION
  - VM API for VMX, [299](#)
- L4\_VM\_VMX\_NUM\_CAPS\_REGS
  - VM API for VMX, [299](#)
- L4\_VM\_VMX\_NUM\_DFL1\_REGS
  - VM API for VMX, [299](#)
- L4\_VM\_VMX\_PINBASED\_CTL5\_DFL1\_REG
  - VM API for VMX, [299](#)
- L4\_VM\_VMX\_PROCBASED\_CTL52\_REG
  - VM API for VMX, [299](#)
- L4\_VM\_VMX\_PROCBASED\_CTL5\_DFL1\_REG
  - VM API for VMX, [299](#)
- l4\_vm\_vmx\_ptr\_load
  - VM API for VMX, [305](#)
- l4\_vm\_vmx\_read
  - VM API for VMX, [306](#)
- l4\_vm\_vmx\_read\_16
  - VM API for VMX, [307](#)
- l4\_vm\_vmx\_read\_32
  - VM API for VMX, [307](#)
- l4\_vm\_vmx\_read\_64
  - VM API for VMX, [308](#)

- `l4_vm_vmx_read_nat`  
VM API for VMX, [308](#)
- `l4_vm_vmx_set_hw_vmcs`  
VM API for VMX, [309](#)
- `L4_vm_vmx_sw_fields`  
VM API for VMX, [299](#)
- `L4_VM_VMX_TRUE_ENTRY_CTLTS_REG`  
VM API for VMX, [299](#)
- `L4_VM_VMX_TRUE_EXIT_CTLTS_REG`  
VM API for VMX, [299](#)
- `L4_VM_VMX_TRUE_PINBASED_CTLTS_REG`  
VM API for VMX, [299](#)
- `L4_VM_VMX_TRUE_PROCBASED_CTLTS_REG`  
VM API for VMX, [299](#)
- `l4_vm_vmx_vcpu_infos_t`, [1564](#)  
`dfi1`, [1565](#)
- `l4_vm_vmx_vcpu_state_t`, [1565](#)  
VM API for VMX, [296](#)
- `l4_vm_vmx_vcpu_vmcs_t`, [1567](#)  
VM API for VMX, [297](#)
- `L4_VM_VMX_VMCS_CR2`  
VM API for VMX, [300](#)
- `L4_VM_VMX_VMCS_ENUM_REG`  
VM API for VMX, [299](#)
- `L4_VM_VMX_VMCS_MSR_CSTAR`  
VM API for VMX, [300](#)
- `L4_VM_VMX_VMCS_MSR_KERNEL_GS_BASE`  
VM API for VMX, [300](#)
- `L4_VM_VMX_VMCS_MSR_LSTAR`  
VM API for VMX, [300](#)
- `L4_VM_VMX_VMCS_MSR_STAR`  
VM API for VMX, [300](#)
- `L4_VM_VMX_VMCS_MSR_SYSCALL_MASK`  
VM API for VMX, [300](#)
- `L4_VM_VMX_VMCS_MSR_TSC_AUX`  
VM API for VMX, [300](#)
- `L4_VM_VMX_VMCS_NAT_ARG0`  
VM API for VMX, [300](#)
- `L4_VM_VMX_VMCS_NAT_ARG1`  
VM API for VMX, [300](#)
- `L4_VM_VMX_VMCS_NAT_ARG2`  
VM API for VMX, [300](#)
- `L4_VM_VMX_VMCS_NAT_ARG3`  
VM API for VMX, [300](#)
- `L4_VM_VMX_VMCS_SIZE_DIRTY_BITMAP`  
VM API for VMX, [300](#)
- `L4_VM_VMX_VMCS_SIZE_VALUES`  
VM API for VMX, [300](#)
- `L4_vm_vmx_vmcs_sizes`  
VM API for VMX, [300](#)
- `L4_VM_VMX_VMCS_XCR0`  
VM API for VMX, [300](#)
- `l4_vm_vmx_write`  
VM API for VMX, [310](#)
- `l4_vm_vmx_write_16`  
VM API for VMX, [311](#)
- `l4_vm_vmx_write_32`  
VM API for VMX, [312](#)
- `l4_vm_vmx_write_64`  
VM API for VMX, [312](#)
- `l4_vm_vmx_write_nat`  
VM API for VMX, [313](#)
- `l4_vmx_offset_table_t`, [1568](#)  
VM API for VMX, [297](#)
- `L4_WHOLE_ADDRESS_SPACE`  
Flexpages, [175](#)
- `L4_WHOLE_IOADDRESS_SPACE`  
Flexpages, [176](#)
- `L4drivers::Mmio_register_block< MAX_BITS >`, [1570](#)
- `L4drivers::Register_block< MAX_BITS, BLOCK >`,  
[1572](#)  
operator[], [1573](#), [1574](#)  
r, [1574](#), [1575](#)
- `L4drivers::Register_block_base< MAX_BITS >`, [1576](#)
- `L4drivers::Register_block_impl< BASE, MAX_BITS >`,  
[1577](#)
- `L4drivers::Register_block_tmpl< BLOCK >`, [1579](#)
- `L4drivers::Register_tmpl< BITS, BLOCK >`, [1580](#)  
clear, [1583](#)  
modify, [1583](#)  
operator=, [1584](#)  
set, [1584](#)  
write, [1585](#)
- `L4drivers::Ro_register_block< MAX_BITS, BLOCK >`,  
[1586](#)  
operator[], [1587](#)  
r, [1587](#)
- `L4drivers::Ro_register_tmpl< BITS, BLOCK >`, [1588](#)  
operator value\_type, [1590](#)  
read, [1590](#)
- `L4IO_DEVICE_ANY`  
IO interface, [452](#)
- `L4IO_DEVICE_INVALID`  
IO interface, [452](#)
- `L4IO_DEVICE_OTHER`  
IO interface, [452](#)
- `L4IO_DEVICE_PCI`  
IO interface, [452](#)
- `l4io_device_types_t`  
IO interface, [451](#)
- `L4IO_DEVICE_USB`  
IO interface, [452](#)
- `l4io_get_root_device`  
io.h, [2556](#)
- `l4io_has_resource`  
IO interface, [453](#)
- `l4io_iomem_flags_t`  
IO interface, [452](#)
- `l4io_iterate_devices`  
io.h, [2556](#)
- `l4io_lookup_device`  
IO interface, [453](#)
- `l4io_lookup_resource`  
IO interface, [453](#)
- `L4IO_MEM_CACHED`  
IO interface, [452](#)

- L4IO\_MEM\_EAGER\_MAP
  - IO interface, [452](#)
- L4IO\_MEM\_NONCACHED
  - IO interface, [452](#)
- L4IO\_MEM\_USE\_MTRR
  - IO interface, [452](#)
- L4IO\_MEM\_USE\_RESERVED\_AREA
  - IO interface, [452](#)
- l4io\_release\_iomem
  - IO interface, [454](#)
- l4io\_release\_ioport
  - IO interface, [454](#)
- l4io\_request\_all\_ioports
  - io.h, [2556](#)
- l4io\_request\_icu
  - io.h, [2557](#)
- l4io\_request\_iomem
  - IO interface, [455](#)
- l4io\_request\_iomem\_region
  - IO interface, [456](#)
- l4io\_request\_ioport
  - IO interface, [456](#)
- l4io\_request\_resource\_iomem
  - IO interface, [457](#)
- L4IO\_RESOURCE\_ANY
  - IO interface, [452](#)
- L4IO\_RESOURCE\_INVALID
  - IO interface, [452](#)
- L4IO\_RESOURCE\_IRQ
  - IO interface, [452](#)
- L4IO\_RESOURCE\_MEM
  - IO interface, [452](#)
- L4IO\_RESOURCE\_PORT
  - IO interface, [452](#)
- l4io\_resource\_t
  - IO interface, [451](#)
- l4io\_resource\_types\_t
  - IO interface, [452](#)
- l4irq\_attach
  - Interface using direct functionality., [461](#)
- l4irq\_attach\_cap
  - Interface using direct functionality., [465](#)
- l4irq\_attach\_cap\_ft
  - Interface using direct functionality., [465](#)
- l4irq\_attach\_ft
  - Interface using direct functionality., [461](#)
- l4irq\_attach\_thread
  - Interface using direct functionality., [461](#)
- l4irq\_attach\_thread\_cap
  - Interface using direct functionality., [466](#)
- l4irq\_attach\_thread\_cap\_ft
  - Interface using direct functionality., [466](#)
- l4irq\_attach\_thread\_ft
  - Interface using direct functionality., [462](#)
- l4irq\_detach
  - Interface using direct functionality., [462](#)
- l4irq\_release
  - Interface for asynchronous ISR handlers., [468](#)
- l4irq\_request
  - Interface for asynchronous ISR handlers., [468](#)
- l4irq\_request\_cap
  - Interface for asynchronous ISR handlers with a given IRQ capability., [470](#)
- l4irq\_unmask
  - Interface using direct functionality., [463](#)
- l4irq\_unmask\_and\_wait\_any
  - Interface using direct functionality., [463](#)
- l4irq\_wait
  - Interface using direct functionality., [464](#)
- l4irq\_wait\_any
  - Interface using direct functionality., [464](#)
- l4la\_alloc
  - list\_alloc.h, [3353](#)
- l4la\_avail
  - list\_alloc.h, [3353](#)
- l4la\_dump
  - list\_alloc.h, [3353](#)
- l4la\_free
  - list\_alloc.h, [3354](#)
- l4la\_init
  - list\_alloc.h, [3354](#)
- l4mod.h
  - L4util\_l4mod\_mod\_flag\_kernel, [3351](#)
  - L4util\_l4mod\_mod\_flag\_mask, [3351](#)
  - L4util\_l4mod\_mod\_flag\_roottask, [3351](#)
  - L4util\_l4mod\_mod\_flag\_sigma0, [3351](#)
  - L4util\_l4mod\_mod\_flag\_unspec, [3351](#)
  - L4util\_l4mod\_mod\_info\_flag, [3351](#)
- L4Re, [760](#)
  - chkcapp, [765](#)
  - chkipc, [766](#)
  - chksys, [767](#), [768](#)
  - make\_shared\_cap, [770](#)
  - make\_shared\_del\_cap, [771](#)
  - make\_unique\_cap, [772](#)
  - make\_unique\_del\_cap, [772](#)
  - Shared\_cap, [763](#)
  - Shared\_del\_cap, [763](#)
  - throw\_error, [773](#)
  - Unique\_cap, [763](#)
  - Unique\_del\_cap, [764](#)
- L4Re Build System, [33](#)
- L4Re C Interface, [516](#)
- L4Re C++ Interface, [574](#)
- L4Re Capability API, [577](#)
  - cap\_alloc, [579](#)
  - make\_ref\_cap, [578](#)
  - make\_ref\_del\_cap, [578](#)
- L4Re ELF Auxiliary Information, [582](#)
  - L4RE\_ELF\_AUX\_ELEM, [583](#)
  - L4RE\_ELF\_AUX\_ELEM\_T, [583](#)
  - L4RE\_ELF\_AUX\_T\_EX\_REGS\_FLAGS, [584](#)
  - L4RE\_ELF\_AUX\_T\_KIP\_ADDR, [584](#)
  - L4RE\_ELF\_AUX\_T\_NONE, [584](#)
  - L4RE\_ELF\_AUX\_T\_STACK\_ADDR, [584](#)
  - L4RE\_ELF\_AUX\_T\_STACK\_SIZE, [584](#)

- L4RE\_ELF\_AUX\_T\_VMA, 584
- L4Re Protocol identifiers, 588
  - L4RE\_PROTO\_DATASPACE, 589
  - L4RE\_PROTO\_DEBUG, 589
  - L4RE\_PROTO\_DMA\_SPACE, 589
  - L4RE\_PROTO\_EVENT, 589
  - L4RE\_PROTO\_GOOS, 589
  - L4RE\_PROTO\_INHIBITOR, 589
  - L4RE\_PROTO\_ITAS, 589
  - L4RE\_PROTO\_MEM\_ALLOC, 589
  - L4RE\_PROTO\_MMIO\_SPACE, 589
  - L4RE\_PROTO\_NAMESPACE, 589
  - L4RE\_PROTO\_PARENT, 589
  - L4RE\_PROTO\_REMOTE\_ACCESS, 589
  - L4RE\_PROTO\_RM, 589
  - L4RE\_PROTO\_RSVD\_1, 589
  - L4re\_protocols, 589
- L4Re Servers, 49
- L4Re Util C Interface, 518
- L4Re Util C++ Interface, 576
- L4Re::Cap\_alloc, 1591
  - alloc, 1592, 1593
  - free, 1593
- L4Re::Console, 1594
- L4Re::Core::Ref\_ptr< T, CNT >, 1597
  - get, 1601
  - ptr, 1601
  - Ref\_ptr, 1600
  - release, 1601
- L4Re::Dataspace, 1602
  - allocate, 1605
  - clear, 1606
  - copy\_in, 1607
  - flags, 1608
  - info, 1609
  - map, 1610
  - map\_info, 1612
  - map\_region, 1613
  - size, 1614
- L4Re::Dataspace::F, 1615
  - Bufferable, 1616
  - Cacheable, 1616
  - Caching\_mask, 1616
  - Caching\_shift, 1615
  - Flags, 1615
  - Normal, 1616
  - R, 1616
  - Rights\_mask, 1616
  - Ro, 1616
  - RW, 1616
  - RWX, 1616
  - RX, 1616
  - Uncacheable, 1616
  - W, 1616
  - X, 1616
- L4Re::Dataspace::Stats, 1616
- L4Re::Debug\_obj, 1617
  - debug, 1620
- L4Re::Default\_event\_payload, 1621
- L4Re::Dma\_space, 1622
  - associate, 1626
  - Attribute, 1624
  - Attributes, 1624
  - Bidirectional, 1625
  - Coherent, 1625
  - Direction, 1625
  - disassociate, 1626
  - From\_device, 1625
  - map, 1627
  - No\_sync, 1625
  - None, 1625
  - Phys\_space, 1625
  - Space\_attrib, 1625
  - To\_device, 1625
  - unmap, 1628
- L4Re::Env, 1629
  - dbg\_events, 1633
  - env, 1633
  - factory, 1634, 1635
  - first\_free\_cap, 1635
  - first\_free\_utcb, 1636
  - get, 1636
  - get\_cap, 1637, 1638
  - initial\_caps, 1639
  - itas, 1640
  - log, 1640
  - main\_thread, 1641
  - mem\_alloc, 1641
  - parent, 1642
  - rm, 1642
  - scheduler, 1643
  - task, 1643
  - utcb\_area, 1643, 1644
- L4Re::Event, 1644
  - get\_axis\_info, 1648
  - get\_buffer, 1649
  - get\_num\_streams, 1650
  - get\_stream\_info, 1651
  - get\_stream\_info\_for\_id, 1652
  - get\_stream\_state\_for\_id, 1653
- L4Re::Event\_buffer\_t< PAYLOAD >, 1654
  - Event\_buffer\_t, 1657
  - next, 1657
  - put, 1657
- L4Re::Event\_buffer\_t< PAYLOAD >::Event, 1658
- L4Re::Inhibitor, 1659
  - acquire, 1662
  - Name\_max, 1662
  - next\_lock\_info, 1663
  - release, 1664
- L4Re::Itas, 1665
  - getitimer, 1668
  - Ignore\_sigaction, 1668
  - raise, 1669
  - register\_thread, 1670
  - setitimer, 1670

- sigaction, [1671](#)
- sigaltstack, [1671](#)
- sigpending, [1672](#)
- sigprocmask, [1673](#)
- unregister\_thread, [1674](#)
- L4Re::Log, [1675](#)
  - print, [1680](#)
  - println, [1680](#)
- L4Re::Mem\_alloc, [1681](#)
  - alloc, [1685](#)
  - Continuous, [1685](#)
  - Fixed\_paddr, [1685](#)
  - info, [1686](#)
  - Mem\_alloc\_flags, [1685](#)
  - Pinned, [1685](#)
  - Super\_pages, [1685](#)
- L4Re::Mem\_alloc::Stats, [1687](#)
  - mem\_free, [1688](#)
  - mem\_limit, [1688](#)
  - mem\_used, [1688](#)
  - quota, [1689](#)
  - quota\_used, [1689](#)
- L4Re::Mmio\_space, [1690](#)
  - Access\_width, [1693](#)
  - mmio\_read, [1693](#)
  - mmio\_write, [1694](#)
  - Wd\_16bit, [1693](#)
  - Wd\_32bit, [1693](#)
  - Wd\_64bit, [1693](#)
  - Wd\_8bit, [1693](#)
- L4Re::Namespace, [1695](#)
  - Link, [1700](#)
  - Overwrite, [1700](#)
  - Partly\_resolved, [1699](#)
  - query, [1700](#), [1701](#)
  - Query\_result\_flags, [1699](#)
  - Query\_timeout, [1699](#)
  - Register\_flags, [1699](#)
  - register\_obj, [1702](#)
  - Ro, [1700](#)
  - Rs, [1700](#)
  - Rw, [1700](#)
  - Rws, [1700](#)
  - Strong, [1700](#)
  - To\_default, [1699](#)
  - To\_non\_blocking, [1699](#)
  - Trusted, [1700](#)
  - unlink, [1703](#)
- L4Re::Ned::Cmd\_control, [1705](#)
  - execute, [1706](#)
- L4Re::Parent, [1707](#)
  - signal, [1710](#)
- L4Re::Random, [1712](#)
  - get\_random, [1715](#)
- L4Re::Rm, [1716](#)
  - attach, [1722](#), [1724](#)
  - Caching\_shift, [1722](#)
  - detach, [1726–1728](#)
  - Detach\_again, [1722](#)
  - Detach\_exact, [1721](#)
  - Detach\_flags, [1721](#)
  - Detach\_keep, [1721](#)
  - Detach\_overlap, [1721](#)
  - Detach\_result, [1721](#)
  - Detached\_ds, [1722](#)
  - find, [1729](#)
  - free\_area, [1730](#)
  - get\_areas, [1731](#)
  - get\_info, [1732](#)
  - get\_regions, [1733](#)
  - Kept\_ds, [1722](#)
  - Region\_flag\_shifts, [1722](#)
  - reserve\_area, [1734](#), [1735](#)
  - Split\_ds, [1722](#)
- L4Re::Rm::Area, [1737](#)
- L4Re::Rm::F, [1737](#)
  - Attach\_flags, [1738](#)
  - Attach\_mask, [1738](#)
  - Cache\_buffered, [1739](#)
  - Cache\_normal, [1739](#)
  - Cache\_uncached, [1739](#)
  - Caching\_mask, [1739](#)
  - Detach\_free, [1739](#)
  - Ds\_map\_mask, [1739](#)
  - Eager\_map, [1738](#)
  - In\_area, [1738](#)
  - Kernel, [1739](#)
  - No\_eager\_map, [1738](#)
  - Pager, [1739](#)
  - R, [1739](#)
  - Region\_flags, [1738](#)
  - Region\_flags\_mask, [1739](#)
  - Reserved, [1739](#)
  - Rights\_mask, [1739](#)
  - RW, [1739](#)
  - RWX, [1739](#)
  - RX, [1739](#)
  - Search\_addr, [1738](#)
  - W, [1739](#)
  - X, [1739](#)
- L4Re::Rm::Region, [1739](#)
- L4Re::Rm::Unique\_region< T >, [1740](#)
  - ~Unique\_region, [1743](#)
  - get, [1744](#)
  - is\_valid, [1744](#)
  - operator=, [1744](#)
  - release, [1745](#)
  - reset, [1745](#)
  - Unique\_region, [1742](#), [1743](#)
- L4Re::Smart\_cap\_auto< Unmap\_flags >, [1746](#)
- L4Re::Smart\_count\_cap< Unmap\_flags >, [1746](#)
- L4Re::Util, [1775](#)
  - make\_shared\_cap, [780](#)
  - make\_shared\_del\_cap, [781](#)
  - make\_unique\_cap, [781](#)
  - make\_unique\_del\_cap, [781](#)

- Shared\_cap, 778
- Shared\_del\_cap, 778
- Unique\_cap, 779
- Unique\_del\_cap, 779
- L4Re::Util::\_Cap\_alloc, 1748
  - alloc, 1750
  - free, 1750
- L4Re::Util::Bitmap< BITS >, 1751
  - scan\_zero, 1755
- L4Re::Util::Bitmap\_base, 1756
  - atomic\_clear\_bit, 1759
  - atomic\_get\_and\_clear, 1759
  - atomic\_get\_and\_set, 1759
  - atomic\_set\_bit, 1760
  - bit, 1760
  - bit\_index, 1761
  - C\_bits, 1759
  - clear\_bit, 1761
  - operator[], 1761, 1762
  - scan\_zero, 1762
  - set\_bit, 1763
  - W\_bits, 1759
  - word\_index, 1763
- L4Re::Util::Bitmap\_base::Bit, 1764
- L4Re::Util::Bitmap\_base::Char< BITS >, 1764
- L4Re::Util::Bitmap\_base::Word< BITS >, 1765
- L4Re::Util::Br\_manager, 1766
  - alloc\_buffer\_demand, 1770
  - get\_rcv\_cap, 1770
  - realloc\_rcv\_cap, 1770
  - set\_rcv\_cap\_flags, 1771
- L4Re::Util::Br\_manager\_hooks, 1772
- L4Re::Util::Br\_manager\_timeout\_hooks, 1774
- L4Re::Util::Cap\_alloc\_base, 1778
- L4Re::Util::Counter< COUNTER >, 1779
  - dec, 1779
  - inc, 1779
- L4Re::Util::Counter\_atomic< COUNTER >, 1780
  - dec, 1781
  - inc, 1781
- L4Re::Util::Counting\_cap\_alloc< COUNTERTYPE, Dbg >, 1782
  - alloc, 1784
  - Counting\_cap\_alloc, 1783
  - free, 1785
  - release, 1786
  - setup, 1787
  - take, 1787
- L4Re::Util::Dataspace\_svr, 1788
  - allocate, 1789
  - clear, 1790
  - copy, 1790
  - is\_static, 1791
  - map, 1791
  - map\_hook, 1792
  - map\_info, 1793
  - page\_shift, 1793
  - release, 1794
- take, 1794
- L4Re::Util::Event\_buffer\_consumer\_t< PAYLOAD >, 1795
  - foreach\_available\_event, 1797
  - process, 1797
- L4Re::Util::Event\_buffer\_t< PAYLOAD >, 1798
  - attach, 1801
  - buf, 1801
  - detach, 1801
- L4Re::Util::Event\_svr< SVR >, 1802
- L4Re::Util::Event\_t< PAYLOAD >, 1804
  - buffer, 1806
  - init, 1806
  - init\_poll, 1807
  - irq, 1807
  - Mode, 1806
  - Mode\_irq, 1806
  - Mode\_polling, 1806
- L4Re::Util::Item\_alloc\_base, 1808
- L4Re::Util::Names::Name, 1809
- L4Re::Util::Names::Name\_space, 1812
  - alloc\_dynamic\_entry, 1813
  - copy\_receive\_cap, 1814
  - free\_capability, 1814
  - free\_dynamic\_entry, 1815
  - free\_epiface, 1815
  - get\_epiface, 1816
- L4Re::Util::Object\_registry, 1817
  - Object\_registry, 1820
  - register\_irq\_obj, 1821
  - register\_obj, 1821, 1822
  - unregister\_obj, 1823
- L4Re::Util::Ref\_cap< T >, 1824
- L4Re::Util::Ref\_del\_cap< T >, 1826
- L4Re::Util::Registry\_server< LOOP\_HOOKS >, 1827
  - loop, 1831
  - loop\_dbg, 1832
  - Registry\_server, 1830, 1831
- L4Re::Util::Smart\_cap\_auto< Unmap\_flags >, 1833
- L4Re::Util::Smart\_count\_cap< Unmap\_flags >, 1834
- L4Re::Util::Vcon\_svr< SVR >, 1835
- L4Re::Util::Video::Goos\_svr, 1836
  - get\_fb, 1838
  - init\_infos, 1838
  - refresh, 1838
  - screen\_info, 1839
  - view\_info, 1839
- L4Re::Vfs, 782
- L4Re::Vfs::Be\_file, 1840
  - check\_ready, 1843
  - data\_space, 1843
  - fstat, 1843
  - unlock\_all\_locks, 1844
- L4Re::Vfs::Be\_file\_system, 1845
  - ~Be\_file\_system, 1847
  - Be\_file\_system, 1847
  - type, 1847
- L4Re::Vfs::Directory, 1848

- faccessat, [1850](#)
  - link, [1850](#)
  - mkdir, [1850](#)
  - rename, [1851](#)
  - rmdir, [1851](#)
  - symlink, [1852](#)
  - unlink, [1852](#)
- L4Re::Vfs::File, [1853](#)
- L4Re::Vfs::File\_system, [1857](#)
  - mount, [1858](#)
  - type, [1859](#)
- L4Re::Vfs::Fs, [1859](#)
  - alloc\_fd, [1862](#)
  - free\_fd, [1862](#)
  - get\_file, [1862](#)
  - mount, [1863](#)
  - set\_fd, [1864](#)
- L4Re::Vfs::Generic\_file, [1864](#)
  - check\_ready, [1867](#)
  - fchmod, [1868](#)
  - fstat, [1868](#)
  - get\_status\_flags, [1869](#)
  - Ready\_type, [1867](#)
  - set\_status\_flags, [1870](#)
  - unlock\_all\_locks, [1871](#)
- L4Re::Vfs::Mman, [1873](#)
- L4Re::Vfs::Ops, [1874](#)
- L4Re::Vfs::Regular\_file, [1877](#)
  - data\_space, [1880](#)
  - fdasync, [1880](#)
  - fsync, [1880](#)
  - ftruncate, [1881](#)
  - get\_lock, [1882](#)
  - lseek, [1883](#)
  - readv, [1884](#)
  - set\_lock, [1885](#)
  - writev, [1886](#)
- L4Re::Vfs::Special\_file, [1887](#)
  - ioctl, [1889](#)
- L4Re::Video::Color\_component, [1890](#)
  - Color\_component, [1891](#)
  - dump, [1891](#)
  - get, [1892](#)
  - operator==, [1892](#)
  - set, [1893](#)
  - shift, [1893](#)
  - size, [1894](#)
- L4Re::Video::Goos, [1895](#)
  - create\_buffer, [1899](#)
  - create\_view, [1899](#)
  - delete\_buffer, [1900](#)
  - delete\_view, [1901](#)
  - F\_auto\_refresh, [1898](#)
  - F\_dynamic\_buffers, [1898](#)
  - F\_dynamic\_views, [1898](#)
  - F\_pointer, [1898](#)
  - Flags, [1898](#)
  - get\_static\_buffer, [1902](#)
  - info, [1903](#)
  - view, [1904](#)
- L4Re::Video::Goos::Info, [1905](#)
- L4Re::Video::Pixel\_info, [1907](#)
  - a, [1911](#)
  - b, [1911](#), [1912](#)
  - bits\_per\_pixel, [1912](#)
  - bytes\_per\_pixel, [1913](#)
  - dump, [1914](#)
  - g, [1915](#)
  - has\_alpha, [1915](#)
  - operator==, [1915](#)
  - padding, [1916](#)
  - Pixel\_info, [1909](#), [1910](#)
  - r, [1916](#), [1917](#)
- L4Re::Video::View, [1918](#)
  - F\_above, [1920](#)
  - F\_dyn\_allocated, [1920](#)
  - F\_flags\_mask, [1920](#)
  - F\_fully\_dynamic, [1920](#)
  - F\_none, [1919](#)
  - F\_set\_background, [1920](#)
  - F\_set\_buffer, [1919](#)
  - F\_set\_buffer\_offset, [1919](#)
  - F\_set\_bytes\_per\_line, [1919](#)
  - F\_set\_flags, [1920](#)
  - F\_set\_pixel, [1920](#)
  - F\_set\_position, [1920](#)
  - Flags, [1919](#)
  - info, [1920](#)
  - refresh, [1921](#)
  - set\_info, [1922](#)
  - set\_viewport, [1923](#)
  - stack, [1924](#)
  - V\_flags, [1920](#)
- L4Re::Video::View::Info, [1925](#)
- l4re\_aux\_t, [1927](#)
- l4re\_debug\_obj\_debug
  - Debug interface, [524](#)
- l4re\_dma\_space\_associate
  - DMA Space Interface, [526](#)
- L4RE\_DMA\_SPACE\_BIDIRECTIONAL
  - dma\_space.h, [2813](#)
- L4RE\_DMA\_SPACE\_COHERENT
  - dma\_space.h, [2814](#)
- l4re\_dma\_space\_direction
  - dma\_space.h, [2813](#)
- l4re\_dma\_space\_disassociate
  - DMA Space Interface, [527](#)
- L4RE\_DMA\_SPACE\_FROM\_DEVICE
  - dma\_space.h, [2813](#)
- l4re\_dma\_space\_map
  - DMA Space Interface, [527](#)
- L4RE\_DMA\_SPACE\_NONE
  - dma\_space.h, [2813](#)
- L4RE\_DMA\_SPACE\_PHYS\_SPACE
  - dma\_space.h, [2814](#)
- l4re\_dma\_space\_space\_attribs



- dma\_space.h, [2813](#)
- l4re\_dma\_space\_t
  - DMA Space Interface, [526](#)
- L4RE\_DMA\_SPACE\_TO\_DEVICE
  - dma\_space.h, [2813](#)
- l4re\_dma\_space\_unmap
  - DMA Space Interface, [528](#)
- l4re\_ds\_allocate
  - Dataspace interface, [520](#)
- l4re\_ds\_clear
  - Dataspace interface, [520](#)
- l4re\_ds\_copy\_in
  - Dataspace interface, [521](#)
- L4RE\_DS\_F\_BUFFERABLE
  - Dataspace interface, [519](#)
- L4RE\_DS\_F\_CACHEABLE
  - Dataspace interface, [519](#)
- L4RE\_DS\_F\_CACHING\_MASK
  - Dataspace interface, [519](#)
- L4RE\_DS\_F\_CACHING\_SHIFT
  - Dataspace interface, [519](#)
- L4RE\_DS\_F\_NORMAL
  - Dataspace interface, [519](#)
- L4RE\_DS\_F\_UNCACHEABLE
  - Dataspace interface, [519](#)
- l4re\_ds\_flags
  - Dataspace interface, [521](#)
- l4re\_ds\_info
  - Dataspace interface, [522](#)
- l4re\_ds\_map\_flags
  - Dataspace interface, [519](#)
- l4re\_ds\_map\_info
  - Dataspace interface, [522](#)
- l4re\_ds\_size
  - Dataspace interface, [523](#)
- l4re\_ds\_stats\_t, [1928](#)
- L4RE\_ELF\_AUX\_ELEM
  - L4Re ELF Auxiliary Information, [583](#)
- L4RE\_ELF\_AUX\_ELEM\_T
  - L4Re ELF Auxiliary Information, [583](#)
- l4re\_elf\_aux\_mword\_t, [1928](#)
- l4re\_elf\_aux\_t, [1929](#)
- L4RE\_ELF\_AUX\_T\_EX\_REGS\_FLAGS
  - L4Re ELF Auxiliary Information, [584](#)
- L4RE\_ELF\_AUX\_T\_KIP\_ADDR
  - L4Re ELF Auxiliary Information, [584](#)
- L4RE\_ELF\_AUX\_T\_NONE
  - L4Re ELF Auxiliary Information, [584](#)
- L4RE\_ELF\_AUX\_T\_STACK\_ADDR
  - L4Re ELF Auxiliary Information, [584](#)
- L4RE\_ELF\_AUX\_T\_STACK\_SIZE
  - L4Re ELF Auxiliary Information, [584](#)
- L4RE\_ELF\_AUX\_T\_VMA
  - L4Re ELF Auxiliary Information, [584](#)
- l4re\_elf\_aux\_vma\_t, [1930](#)
- l4re\_env
  - Initial Environment, [570](#)
- l4re\_env\_cap\_entry\_t, [1930](#)
  - flags, [1932](#)
  - l4re\_env\_cap\_entry\_t, [1931](#)
- l4re\_env\_get\_cap
  - Initial Environment, [571](#)
- l4re\_env\_get\_cap\_e
  - Initial Environment, [571](#)
- l4re\_env\_get\_cap\_l
  - Initial Environment, [572](#)
- l4re\_env\_t, [1932](#)
  - caps, [1934](#)
  - env.h, [2859](#)
- l4re\_event\_get\_axis\_info
  - Event interface, [530](#)
- l4re\_event\_get\_buffer
  - Event interface, [530](#)
- l4re\_event\_get\_num\_streams
  - Event interface, [530](#)
- l4re\_event\_get\_stream\_info
  - Event interface, [531](#)
- l4re\_event\_get\_stream\_info\_for\_id
  - Event interface, [531](#)
- l4re\_event\_t, [1935](#)
- l4re\_inhibitor\_acquire
  - inhibitor.h, [2820](#)
- l4re\_inhibitor\_next\_lock\_info
  - inhibitor.h, [2821](#)
- l4re\_inhibitor\_release
  - inhibitor.h, [2821](#)
- l4re\_kip
  - Initial Environment, [573](#)
- l4re\_log\_print
  - Log interface, [533](#)
- l4re\_log\_print\_srv
  - Log interface, [533](#)
- l4re\_log\_printn
  - Log interface, [534](#)
- l4re\_log\_printn\_srv
  - Log interface, [534](#)
- l4re\_ma\_alloc
  - Memory allocator, [536](#)
- l4re\_ma\_alloc\_align
  - Memory allocator, [537](#)
- l4re\_ma\_alloc\_align\_srv
  - Memory allocator, [539](#)
- l4re\_ma\_flags
  - Memory allocator, [536](#)
- l4re\_ns\_query\_srv
  - Namespace interface, [541](#)
- l4re\_ns\_query\_to\_srv
  - Namespace interface, [542](#)
- l4re\_ns\_register\_flags
  - Namespace interface, [541](#)
- l4re\_ns\_register\_obj\_srv
  - Namespace interface, [543](#)
- l4re\_parent\_signal
  - parent.h, [2828](#)
- L4RE\_PROTO\_DATASPACE
  - L4Re Protocol identifiers, [589](#)



- L4RE\_PROTO\_DEBUG
  - L4Re Protocol identifiers, [589](#)
- L4RE\_PROTO\_DMA\_SPACE
  - L4Re Protocol identifiers, [589](#)
- L4RE\_PROTO\_EVENT
  - L4Re Protocol identifiers, [589](#)
- L4RE\_PROTO\_GOOS
  - L4Re Protocol identifiers, [589](#)
- L4RE\_PROTO\_INHIBITOR
  - L4Re Protocol identifiers, [589](#)
- L4RE\_PROTO\_ITAS
  - L4Re Protocol identifiers, [589](#)
- L4RE\_PROTO\_MEM\_ALLOC
  - L4Re Protocol identifiers, [589](#)
- L4RE\_PROTO\_MMIO\_SPACE
  - L4Re Protocol identifiers, [589](#)
- L4RE\_PROTO\_NAMESPACE
  - L4Re Protocol identifiers, [589](#)
- L4RE\_PROTO\_PARENT
  - L4Re Protocol identifiers, [589](#)
- L4RE\_PROTO\_REMOTE\_ACCESS
  - L4Re Protocol identifiers, [589](#)
- L4RE\_PROTO\_RM
  - L4Re Protocol identifiers, [589](#)
- L4RE\_PROTO\_RSVD\_1
  - L4Re Protocol identifiers, [589](#)
- L4re\_protocols
  - L4Re Protocol identifiers, [589](#)
- l4re\_rm\_attach
  - Region map interface, [546](#)
- l4re\_rm\_attach\_srv
  - Region map interface, [547](#)
- L4RE\_RM\_CACHING\_SHIFT
  - Region map interface, [546](#)
- l4re\_rm\_detach
  - Region map interface, [548](#)
- l4re\_rm\_detach\_ds
  - Region map interface, [549](#)
- l4re\_rm\_detach\_ds\_unmap
  - Region map interface, [550](#)
- l4re\_rm\_detach\_srv
  - Region map interface, [551](#)
- l4re\_rm\_detach\_unmap
  - Region map interface, [551](#)
- L4RE\_RM\_F\_ATTACH\_FLAGS
  - Region map interface, [546](#)
- L4RE\_RM\_F\_CACHE\_BUFFERED
  - Region map interface, [546](#)
- L4RE\_RM\_F\_CACHE\_NORMAL
  - Region map interface, [546](#)
- L4RE\_RM\_F\_CACHE\_UNCACHED
  - Region map interface, [546](#)
- L4RE\_RM\_F\_CACHING
  - Region map interface, [546](#)
- L4RE\_RM\_F\_DETACH\_FREE
  - Region map interface, [546](#)
- L4RE\_RM\_F\_EAGER\_MAP
  - Region map interface, [546](#)
- L4RE\_RM\_F\_IN\_AREA
  - Region map interface, [546](#)
- L4RE\_RM\_F\_KERNEL
  - Region map interface, [546](#)
- L4RE\_RM\_F\_NO\_EAGER\_MAP
  - Region map interface, [546](#)
- L4RE\_RM\_F\_PAGER
  - Region map interface, [546](#)
- L4RE\_RM\_F\_R
  - Region map interface, [546](#)
- L4RE\_RM\_F\_RESERVED
  - Region map interface, [546](#)
- L4RE\_RM\_F\_SEARCH\_ADDR
  - Region map interface, [546](#)
- l4re\_rm\_find
  - Region map interface, [552](#)
- l4re\_rm\_find\_srv
  - Region map interface, [553](#)
- l4re\_rm\_flags\_values
  - Region map interface, [545](#)
- l4re\_rm\_free\_area
  - Region map interface, [554](#)
- l4re\_rm\_free\_area\_srv
  - Region map interface, [555](#)
- l4re\_rm\_get\_info
  - Region map interface, [555](#)
- l4re\_rm\_get\_info\_srv
  - Region map interface, [556](#)
- L4RE\_RM\_REGION\_FLAGS
  - Region map interface, [546](#)
- l4re\_rm\_reserve\_area
  - Region map interface, [557](#)
- l4re\_rm\_reserve\_area\_srv
  - Region map interface, [558](#)
- l4re\_rm\_show\_lists
  - Region map interface, [559](#)
- l4re\_util\_cap\_last
  - Capability allocator, [560](#)
- l4re\_util\_kumem\_alloc
  - kumem\_alloc.h, [2836](#)
- l4re\_video\_color\_component\_t, [1936](#)
- l4re\_video\_goos\_create\_buffer
  - Video API, [563](#)
- l4re\_video\_goos\_create\_view
  - Video API, [564](#)
- l4re\_video\_goos\_delete\_buffer
  - Video API, [564](#)
- l4re\_video\_goos\_delete\_view
  - Video API, [565](#)
- l4re\_video\_goos\_get\_static\_buffer
  - Video API, [565](#)
- l4re\_video\_goos\_get\_view
  - Video API, [565](#)
- l4re\_video\_goos\_info
  - Video API, [566](#)
- l4re\_video\_goos\_info\_flags\_t
  - Video API, [563](#)
- l4re\_video\_goos\_info\_t, [1936](#)

- l4re\_video\_goos\_refresh
  - Video API, [566](#)
- l4re\_video\_pixel\_info\_t, [1938](#)
- l4re\_video\_view\_get\_info
  - Video API, [567](#)
- l4re\_video\_view\_info\_flags\_t
  - Video API, [563](#)
- l4re\_video\_view\_info\_t, [1939](#)
- l4re\_video\_view\_refresh
  - Video API, [567](#)
- l4re\_video\_view\_set\_info
  - Video API, [568](#)
- l4re\_video\_view\_set\_viewport
  - Video API, [568](#)
- l4re\_video\_view\_stack
  - Video API, [569](#)
- l4re\_video\_view\_t, [1941](#)
  - Video API, [562](#)
- L4SHM-based ring buffer implementation, [593](#)
- l4shmc\_add\_chunk
  - Chunks, [603](#)
- l4shmc\_add\_signal
  - Signals, [615](#)
- l4shmc\_area\_overhead
  - Shared Memory Library, [598](#)
- l4shmc\_area\_size
  - Shared Memory Library, [598](#)
- l4shmc\_area\_size\_free
  - Shared Memory Library, [598](#)
- l4shmc\_attach
  - Shared Memory Library, [598](#)
- l4shmc\_attach\_signal
  - Signals, [616](#)
- l4shmc\_check\_magic
  - Signals, [616](#)
- l4shmc\_chunk\_capacity
  - Chunks, [603](#)
- l4shmc\_chunk\_consumed
  - Consumer, [611](#)
- l4shmc\_chunk\_overhead
  - Shared Memory Library, [599](#)
- l4shmc\_chunk\_ptr
  - Chunks, [604](#)
- l4shmc\_chunk\_ready
  - Producer, [607](#)
- l4shmc\_chunk\_ready\_sig
  - Producer, [608](#)
- l4shmc\_chunk\_signal
  - Chunks, [604](#)
- l4shmc\_chunk\_size
  - Consumer, [611](#)
- l4shmc\_chunk\_try\_to\_take
  - Producer, [608](#)
- l4shmc\_chunk\_try\_to\_take\_for\_overwriting
  - Producer, [609](#)
- l4shmc\_chunk\_try\_to\_take\_for\_reading
  - Consumer, [611](#)
- l4shmc\_chunk\_try\_to\_take\_for\_writing
  - Producer, [609](#)
- l4shmc\_connect\_chunk\_signal
  - Shared Memory Library, [599](#)
- l4shmc\_create
  - Shared Memory Library, [600](#)
- l4shmc\_enable\_chunk
  - Consumer, [612](#)
- l4shmc\_enable\_signal
  - Consumer, [620](#)
- l4shmc\_get\_chunk
  - Chunks, [605](#)
- l4shmc\_get\_chunk\_to
  - Chunks, [605](#)
- l4shmc\_get\_client\_nr
  - Shared Memory Library, [600](#)
- l4shmc\_get\_initialized\_clients
  - Shared Memory Library, [601](#)
- l4shmc\_get\_signal
  - Signals, [617](#)
- l4shmc\_is\_chunk\_clear
  - Producer, [610](#)
- l4shmc\_is\_chunk\_ready
  - Consumer, [612](#)
- l4shmc\_iterate\_chunk
  - Chunks, [606](#)
- l4shmc\_mark\_client\_initialized
  - Shared Memory Library, [601](#)
- l4shmc\_rb\_attach\_receiver
  - ringbuf.h, [2985](#)
- l4shmc\_rb\_attach\_sender
  - ringbuf.h, [2985](#)
- l4shmc\_rb\_deinit\_buffer
  - ringbuf.h, [2985](#)
- l4shmc\_rb\_init\_buffer
  - ringbuf.h, [2986](#)
- l4shmc\_rb\_init\_receiver
  - ringbuf.h, [2986](#)
- l4shmc\_rb\_receiver\_copy\_out
  - ringbuf.h, [2987](#)
- l4shmc\_rb\_receiver\_notify\_done
  - ringbuf.h, [2987](#)
- l4shmc\_rb\_receiver\_read\_next\_size
  - ringbuf.h, [2988](#)
- l4shmc\_rb\_receiver\_wait\_for\_data
  - ringbuf.h, [2988](#)
- l4shmc\_rb\_sender\_alloc\_packet
  - ringbuf.h, [2988](#)
- l4shmc\_rb\_sender\_commit\_packet
  - ringbuf.h, [2989](#)
- l4shmc\_rb\_sender\_next\_copy\_in
  - ringbuf.h, [2989](#)
- l4shmc\_rb\_sender\_put\_data
  - ringbuf.h, [2990](#)
- L4SHMC\_RINGBUF\_DATA
  - Internal, [595](#)
- L4SHMC\_RINGBUF\_DATA\_SIZE
  - Internal, [595](#)
- L4SHMC\_RINGBUF\_HEAD

- Internal, [596](#)
- l4shmc\_ringbuf\_head\_t, [1942](#)
- l4shmc\_ringbuf\_t, [1943](#)
- l4shmc\_signal\_cap
  - Signals, [617](#)
- l4shmc\_trigger
  - Producer, [618](#)
- l4shmc\_wait\_any
  - Consumer, [620](#)
- l4shmc\_wait\_any\_to
  - Consumer, [620](#)
- l4shmc\_wait\_any\_try
  - Consumer, [621](#)
- l4shmc\_wait\_chunk
  - Consumer, [613](#)
- l4shmc\_wait\_chunk\_to
  - Consumer, [613](#)
- l4shmc\_wait\_chunk\_try
  - Consumer, [614](#)
- l4shmc\_wait\_signal
  - Consumer, [621](#)
- l4shmc\_wait\_signal\_to
  - Consumer, [622](#)
- l4shmc\_wait\_signal\_try
  - Consumer, [622](#)
- l4sigma0\_debug\_dump
  - Sigma0 API, [625](#)
- L4SIGMA0\_IPCERROR
  - Sigma0 API, [624](#)
- l4sigma0\_map\_anypage
  - Sigma0 API, [625](#)
- l4sigma0\_map\_errstr
  - Sigma0 API, [625](#)
- l4sigma0\_map\_iomem
  - Sigma0 API, [626](#)
- l4sigma0\_map\_kip
  - Sigma0 API, [626](#)
- l4sigma0\_map\_mem
  - Sigma0 API, [627](#)
- L4SIGMA0\_NOFPAGE
  - Sigma0 API, [624](#)
- L4SIGMA0\_NOTALIGNED
  - Sigma0 API, [624](#)
- L4SIGMA0\_OK
  - Sigma0 API, [624](#)
- l4sigma0\_return\_flags\_t
  - Sigma0 API, [624](#)
- L4SIGMA0\_SMALLERFPAGE
  - Sigma0 API, [624](#)
- l4util\_add16
  - Atomic Instructions, [660](#)
- l4util\_add16\_res
  - Atomic Instructions, [660](#)
- l4util\_add32
  - Atomic Instructions, [660](#)
- l4util\_add32\_res
  - Atomic Instructions, [661](#)
- l4util\_add8
  - Atomic Instructions, [661](#)
- l4util\_add8\_res
  - Atomic Instructions, [661](#)
- l4util\_and16
  - Atomic Instructions, [662](#)
- l4util\_and16\_res
  - Atomic Instructions, [662](#)
- l4util\_and32
  - Atomic Instructions, [662](#)
- l4util\_and32\_res
  - Atomic Instructions, [663](#)
- l4util\_and8
  - Atomic Instructions, [663](#)
- l4util\_and8\_res
  - Atomic Instructions, [663](#)
- l4util\_atomic\_add
  - Atomic Instructions, [664](#)
- l4util\_atomic\_inc
  - Atomic Instructions, [664](#)
- l4util\_backtrace
  - backtrace.h, [3314](#)
- l4util\_bsf
  - Bit Manipulation, [677](#)
- l4util\_bsr
  - Bit Manipulation, [678](#)
- l4util\_btc
  - Bit Manipulation, [678](#)
- l4util\_btr
  - Bit Manipulation, [678](#)
- l4util\_bts
  - Bit Manipulation, [679](#)
- l4util\_clear\_bit
  - Bit Manipulation, [680](#)
- l4util\_cmpxchg
  - Atomic Instructions, [664](#)
- l4util\_cmpxchg16
  - Atomic Instructions, [665](#)
- l4util\_cmpxchg32
  - Atomic Instructions, [666](#)
- l4util\_cmpxchg8
  - Atomic Instructions, [666](#)
- l4util\_complement\_bit
  - Bit Manipulation, [680](#)
- l4util\_cpu\_capabilities
  - CPU related functions, [643](#)
- l4util\_cpu\_capabilities\_nocheck
  - CPU related functions, [643](#)
- l4util\_cpu\_has\_cpuid
  - CPU related functions, [644](#)
- l4util\_dec16
  - Atomic Instructions, [667](#)
- l4util\_dec16\_res
  - Atomic Instructions, [667](#)
- l4util\_dec32
  - Atomic Instructions, [667](#)
- l4util\_dec32\_res
  - Atomic Instructions, [668](#)
- l4util\_dec8

- Atomic Instructions, [668](#)
- l4util\_dec8\_res
  - Atomic Instructions, [668](#)
- l4util\_find\_first\_set\_bit
  - Bit Manipulation, [681](#)
- l4util\_find\_first\_zero\_bit
  - Bit Manipulation, [681](#)
- l4util\_in16
  - IA32 Port I/O API, [646](#)
- l4util\_in32
  - IA32 Port I/O API, [646](#)
- l4util\_in8
  - IA32 Port I/O API, [646](#)
- l4util\_inc16
  - Atomic Instructions, [668](#)
- l4util\_inc16\_res
  - Atomic Instructions, [669](#)
- l4util\_inc32
  - Atomic Instructions, [669](#)
- l4util\_inc32\_res
  - Atomic Instructions, [669](#)
- l4util\_inc8
  - Atomic Instructions, [670](#)
- l4util\_inc8\_res
  - Atomic Instructions, [670](#)
- l4util\_ins16
  - IA32 Port I/O API, [647](#)
- l4util\_ins32
  - IA32 Port I/O API, [647](#)
- l4util\_ins8
  - IA32 Port I/O API, [648](#)
- l4util\_ioport\_map
  - IA32 Port I/O API, [648](#)
- l4util\_kip\_for\_each\_feature
  - Kernel Interface Page API, [708](#)
- l4util\_kip\_kernel\_abi\_version
  - Kernel Interface Page API, [709](#)
- l4util\_kip\_kernel\_has\_feature
  - Kernel Interface Page API, [709](#)
- l4util\_l4mod\_info, [1944](#)
  - vbe\_ctrl\_info, [1945](#)
- l4util\_l4mod\_mod, [1946](#)
- L4util\_l4mod\_mod\_flag\_kernel
  - l4mod.h, [3351](#)
- L4util\_l4mod\_mod\_flag\_mask
  - l4mod.h, [3351](#)
- L4util\_l4mod\_mod\_flag\_roottask
  - l4mod.h, [3351](#)
- L4util\_l4mod\_mod\_flag\_sigma0
  - l4mod.h, [3351](#)
- L4util\_l4mod\_mod\_flag\_unspec
  - l4mod.h, [3351](#)
- l4util\_l4mod\_mod\_info\_flag
  - l4mod.h, [3351](#)
- l4util\_mb\_addr\_range\_t, [1947](#)
- l4util\_mb\_apm\_t, [1948](#)
- l4util\_mb\_drive\_t, [1948](#)
- l4util\_mb\_for\_each\_mmap\_entry
  - mb\_info.h, [3360](#)
- l4util\_mb\_info\_t, [1949](#)
- L4UTIL\_MB\_MEMORY
  - mb\_info.h, [3360](#)
- l4util\_mb\_mod\_t, [1951](#)
- l4util\_mb\_vbe\_ctrl\_t, [1952](#)
- l4util\_mb\_vbe\_mode\_t, [1952](#)
- l4util\_micros2l4to
  - Utility Functions, [640](#)
- l4util\_next\_power2
  - Bit Manipulation, [681](#)
- l4util\_or16
  - Atomic Instructions, [670](#)
- l4util\_or16\_res
  - Atomic Instructions, [671](#)
- l4util\_or32
  - Atomic Instructions, [671](#)
- l4util\_or32\_res
  - Atomic Instructions, [671](#)
- l4util\_or8
  - Atomic Instructions, [671](#)
- l4util\_or8\_res
  - Atomic Instructions, [672](#)
- l4util\_out16
  - IA32 Port I/O API, [649](#)
- l4util\_out32
  - IA32 Port I/O API, [649](#)
- l4util\_out8
  - IA32 Port I/O API, [650](#)
- l4util\_outs16
  - IA32 Port I/O API, [650](#)
- l4util\_outs32
  - IA32 Port I/O API, [650](#)
- l4util\_outs8
  - IA32 Port I/O API, [651](#)
- l4util\_rand
  - Random number support, [712](#)
- l4util\_set\_bit
  - Bit Manipulation, [682](#)
- l4util\_splitlog2\_hdl
  - Utility Functions, [640](#)
- l4util\_splitlog2\_size
  - Utility Functions, [641](#)
- l4util\_srand
  - Random number support, [712](#)
- l4util\_sub16
  - Atomic Instructions, [672](#)
- l4util\_sub16\_res
  - Atomic Instructions, [672](#)
- l4util\_sub32
  - Atomic Instructions, [673](#)
- l4util\_sub32\_res
  - Atomic Instructions, [673](#)
- l4util\_sub8
  - Atomic Instructions, [673](#)
- l4util\_sub8\_res
  - Atomic Instructions, [674](#)
- l4util\_test\_bit

- Bit Manipulation, [682](#)
- l4util\_xchg
  - Atomic Instructions, [674](#)
- l4util\_xchg16
  - Atomic Instructions, [674](#)
- l4util\_xchg32
  - Atomic Instructions, [675](#)
- l4util\_xchg8
  - Atomic Instructions, [675](#)
- L4vbus, [783](#)
- L4vbus GPIO functions, [497](#)
  - l4vbus\_gpio\_config\_get, [499](#)
  - l4vbus\_gpio\_config\_pad, [500](#)
  - l4vbus\_gpio\_config\_pull, [500](#)
  - L4vbus\_gpio\_generic\_func, [498](#)
  - l4vbus\_gpio\_get, [501](#)
  - l4vbus\_gpio\_multi\_config\_pad, [502](#)
  - l4vbus\_gpio\_multi\_get, [503](#)
  - l4vbus\_gpio\_multi\_set, [503](#)
  - l4vbus\_gpio\_multi\_setup, [504](#)
  - L4VBUS\_GPIO\_PIN\_PULL\_DOWN, [499](#)
  - L4VBUS\_GPIO\_PIN\_PULL\_NONE, [499](#)
  - L4VBUS\_GPIO\_PIN\_PULL\_UP, [499](#)
  - L4vbus\_gpio\_pull\_modes, [499](#)
  - l4vbus\_gpio\_set, [505](#)
  - l4vbus\_gpio\_setup, [506](#)
  - L4VBUS\_GPIO\_SETUP\_INPUT, [499](#)
  - L4VBUS\_GPIO\_SETUP\_IRQ, [499](#)
  - L4VBUS\_GPIO\_SETUP\_OUTPUT, [499](#)
  - l4vbus\_gpio\_to\_irq, [507](#)
- L4vbus PCI functions, [508](#)
  - l4vbus\_pci\_cfg\_read, [508](#)
  - l4vbus\_pci\_cfg\_write, [509](#)
  - l4vbus\_pci\_irq\_enable, [510](#)
  - l4vbus\_pciddev\_cfg\_read, [511](#)
  - l4vbus\_pciddev\_cfg\_write, [512](#)
  - l4vbus\_pciddev\_irq\_enable, [513](#)
- L4vbus power management functions, [514](#)
  - l4vbus\_pm\_resume, [514](#)
  - l4vbus\_pm\_suspend, [515](#)
- L4vbus::Device, [1956](#)
  - bus\_cap, [1959](#)
  - dev\_handle, [1960](#)
  - Device, [1959](#)
  - device, [1960](#)
  - device\_by\_hid, [1961](#)
  - get\_resource, [1962](#)
  - is\_compatible, [1963](#)
  - next\_device, [1964](#)
  - operator!=, [1964](#)
  - operator==, [1965](#)
- L4vbus::Gpio\_module, [1966](#)
  - config\_pad, [1969](#)
  - get, [1969](#)
  - pin, [1970](#)
  - set, [1971](#)
  - setup, [1972](#)
- L4vbus::Gpio\_module::Pin\_slice, [1973](#)
- L4vbus::Gpio\_pin, [1973](#)
  - config\_get, [1977](#)
  - config\_pad, [1977](#)
  - config\_pull, [1978](#)
  - get, [1979](#)
  - pin, [1979](#)
  - set, [1979](#)
  - setup, [1980](#)
  - to\_irq, [1981](#)
- L4vbus::Icu, [1982](#)
  - Src\_dev\_handle, [1985](#)
  - Src\_types, [1985](#)
  - vicu, [1985](#)
- L4vbus::Pci\_dev, [1986](#)
  - cfg\_read, [1990](#)
  - cfg\_write, [1990](#)
  - irq\_enable, [1991](#)
- L4vbus::Pci\_host\_bridge, [1992](#)
  - cfg\_read, [1996](#)
  - cfg\_write, [1996](#)
  - irq\_enable, [1997](#)
- L4vbus::Pm< DEC >, [1998](#)
  - pm\_resume, [2000](#)
  - pm\_suspend, [2000](#)
- L4vbus::Vbus, [2001](#)
  - assign\_dma\_domain, [2008](#), [2009](#)
  - release\_ioport, [2010](#)
  - request\_ioport, [2010](#)
  - root, [2011](#)
- l4vbus\_assign\_dma\_domain
  - L4 Vbus functions, [489](#)
- L4VBUS\_DEVICE\_F\_CHILDREN
  - vbus\_types.h, [3388](#)
- l4vbus\_device\_flags\_t
  - vbus\_types.h, [3388](#)
- l4vbus\_device\_t, [2012](#)
- L4vbus\_dma\_domain\_assign\_flags
  - L4 Vbus functions, [489](#)
- L4VBUS\_DMAD\_BIND
  - L4 Vbus functions, [489](#)
- L4VBUS\_DMAD\_KERNEL\_DMA\_SPACE
  - L4 Vbus functions, [489](#)
- L4VBUS\_DMAD\_L4RE\_DMA\_SPACE
  - L4 Vbus functions, [489](#)
- L4VBUS\_DMAD\_UNBIND
  - L4 Vbus functions, [489](#)
- l4vbus\_get\_adr
  - L4 Vbus functions, [490](#)
- l4vbus\_get\_device
  - L4 Vbus functions, [490](#)
- l4vbus\_get\_device\_by\_hid
  - L4 Vbus functions, [491](#)
- l4vbus\_get\_hid
  - L4 Vbus functions, [492](#)
- l4vbus\_get\_next\_device
  - L4 Vbus functions, [493](#)
- l4vbus\_get\_resource
  - L4 Vbus functions, [493](#)

- l4vbus\_gpio\_config\_get
  - L4vbus GPIO functions, [499](#)
- l4vbus\_gpio\_config\_pad
  - L4vbus GPIO functions, [500](#)
- l4vbus\_gpio\_config\_pull
  - L4vbus GPIO functions, [500](#)
- L4vbus\_gpio\_generic\_func
  - L4vbus GPIO functions, [498](#)
- l4vbus\_gpio\_get
  - L4vbus GPIO functions, [501](#)
- l4vbus\_gpio\_multi\_config\_pad
  - L4vbus GPIO functions, [502](#)
- l4vbus\_gpio\_multi\_get
  - L4vbus GPIO functions, [503](#)
- l4vbus\_gpio\_multi\_set
  - L4vbus GPIO functions, [503](#)
- l4vbus\_gpio\_multi\_setup
  - L4vbus GPIO functions, [504](#)
- L4VBUS\_GPIO\_PIN\_PULL\_DOWN
  - L4vbus GPIO functions, [499](#)
- L4VBUS\_GPIO\_PIN\_PULL\_NONE
  - L4vbus GPIO functions, [499](#)
- L4VBUS\_GPIO\_PIN\_PULL\_UP
  - L4vbus GPIO functions, [499](#)
- L4vbus\_gpio\_pull\_modes
  - L4vbus GPIO functions, [499](#)
- l4vbus\_gpio\_set
  - L4vbus GPIO functions, [505](#)
- l4vbus\_gpio\_setup
  - L4vbus GPIO functions, [506](#)
- L4VBUS\_GPIO\_SETUP\_INPUT
  - L4vbus GPIO functions, [499](#)
- L4VBUS\_GPIO\_SETUP\_IRQ
  - L4vbus GPIO functions, [499](#)
- L4VBUS\_GPIO\_SETUP\_OUTPUT
  - L4vbus GPIO functions, [499](#)
- l4vbus\_gpio\_to\_irq
  - L4vbus GPIO functions, [507](#)
- L4VBUS\_ICU\_SRC\_DEV\_HANDLE
  - vbus.h, [3375](#)
- l4vbus\_icu\_src\_types
  - vbus.h, [3375](#)
- L4VBUS\_IFACE\_SHIFT
  - vbus\_interfaces.h, [3382](#)
- l4vbus\_iface\_type\_t
  - vbus\_interfaces.h, [3381](#), [3382](#)
- L4VBUS\_INTERFACE\_BUS
  - vbus\_interfaces.h, [3382](#)
- L4VBUS\_INTERFACE\_GENERIC
  - vbus\_interfaces.h, [3382](#)
- L4VBUS\_INTERFACE\_GPIO
  - vbus\_interfaces.h, [3382](#)
- L4VBUS\_INTERFACE\_ICU
  - vbus\_interfaces.h, [3382](#)
- L4VBUS\_INTERFACE\_PCI
  - vbus\_interfaces.h, [3382](#)
- L4VBUS\_INTERFACE\_PCIDEV
  - vbus\_interfaces.h, [3382](#)
- L4VBUS\_INTERFACE\_PM
  - vbus\_interfaces.h, [3382](#)
- l4vbus\_is\_compatible
  - L4 Vbus functions, [494](#)
- L4VBUS\_NULL
  - vbus.h, [3375](#)
- l4vbus\_pci\_cfg\_read
  - L4vbus PCI functions, [508](#)
- l4vbus\_pci\_cfg\_write
  - L4vbus PCI functions, [509](#)
- l4vbus\_pci\_irq\_enable
  - L4vbus PCI functions, [510](#)
- l4vbus\_pciddev\_cfg\_read
  - L4vbus PCI functions, [511](#)
- l4vbus\_pciddev\_cfg\_write
  - L4vbus PCI functions, [512](#)
- l4vbus\_pciddev\_irq\_enable
  - L4vbus PCI functions, [513](#)
- l4vbus\_pm\_resume
  - L4vbus power management functions, [514](#)
- l4vbus\_pm\_suspend
  - L4vbus power management functions, [515](#)
- l4vbus\_release\_ioport
  - L4 Vbus functions, [495](#)
- l4vbus\_request\_ioport
  - L4 Vbus functions, [496](#)
- L4VBUS\_RESOURCE\_BUS
  - vbus\_types.h, [3389](#)
- L4VBUS\_RESOURCE\_DMA\_DOMAIN
  - vbus\_types.h, [3389](#)
- L4VBUS\_RESOURCE\_F\_MEM\_CACHEABLE
  - vbus\_types.h, [3389](#)
- L4VBUS\_RESOURCE\_F\_MEM\_MMIO\_READ
  - vbus\_types.h, [3389](#)
- L4VBUS\_RESOURCE\_F\_MEM\_MMIO\_WRITE
  - vbus\_types.h, [3389](#)
- L4VBUS\_RESOURCE\_F\_MEM\_PREFETCHABLE
  - vbus\_types.h, [3389](#)
- L4VBUS\_RESOURCE\_F\_MEM\_R
  - vbus\_types.h, [3388](#)
- L4VBUS\_RESOURCE\_F\_MEM\_W
  - vbus\_types.h, [3389](#)
- l4vbus\_resource\_flags\_t
  - vbus\_types.h, [3388](#)
- L4VBUS\_RESOURCE\_GPIO
  - vbus\_types.h, [3389](#)
- L4VBUS\_RESOURCE\_INVALID
  - vbus\_types.h, [3389](#)
- L4VBUS\_RESOURCE\_IRQ
  - vbus\_types.h, [3389](#)
- L4VBUS\_RESOURCE\_MAX
  - vbus\_types.h, [3389](#)
- L4VBUS\_RESOURCE\_MEM
  - vbus\_types.h, [3389](#)
- L4VBUS\_RESOURCE\_PORT
  - vbus\_types.h, [3389](#)
- l4vbus\_resource\_t, [2013](#)
- l4vbus\_resource\_type\_t

- vbus\_types.h, 3389
- L4VBUS\_ROOT\_BUS
  - vbus.h, 3375
- l4vbus\_subinterface\_supported
  - vbus\_interfaces.h, 3382
- l4vbus\_vicu\_get\_cap
  - L4 Vbus functions, 496
- L4vcpu::State, 2014
  - add, 2015
  - clear, 2015
  - set, 2016
  - State, 2015
- L4vcpu::Vcpu, 2016
  - cast, 2020
  - entry\_ip, 2021
  - entry\_sp, 2021
  - ext\_alloc, 2022
  - i, 2022, 2023
  - irq\_disable\_save, 2023
  - irq\_enable, 2023
  - irq\_restore, 2024
  - is\_irq\_entry, 2025
  - is\_page\_fault\_entry, 2025
  - r, 2026
  - saved\_state, 2026
  - state, 2027
  - task, 2027
  - wait\_for\_event, 2028
- l4vcpu\_ext\_alloc
  - Extended vCPU support, 722
- l4vcpu\_irq\_disable
  - vCPU Support Library, 715
- l4vcpu\_irq\_disable\_save
  - vCPU Support Library, 716
- l4vcpu\_irq\_enable
  - vCPU Support Library, 716
- l4vcpu\_irq\_restore
  - vCPU Support Library, 717
- l4vcpu\_is\_irq\_entry
  - vCPU Support Library, 718
- l4vcpu\_is\_page\_fault\_entry
  - vCPU Support Library, 719
- l4vcpu\_print\_state
  - vCPU Support Library, 720
- l4vcpu\_wait\_for\_event
  - vCPU Support Library, 720
- L4virtio, 784
- L4virtio::Device, 2029
  - config\_queue, 2034
  - device\_config, 2034
  - device\_notification\_irq, 2035
  - register\_ds, 2036
  - set\_status, 2037
- L4virtio::Driver::Block\_device, 2039
  - add\_block, 2042
  - process\_request, 2042
  - process\_used\_queue, 2043
  - send\_request, 2044
  - setup\_device, 2044
  - start\_request, 2046
- L4virtio::Driver::Block\_device::Handle, 2047
- L4virtio::Driver::Device, 2047
  - bind\_notification\_irq, 2050
  - config\_queue, 2051
  - driver\_acknowledge, 2051
  - driver\_connect, 2052
  - feature\_negotiated, 2054
  - max\_queue\_size, 2054
  - register\_ds, 2055
  - send, 2056
  - send\_and\_wait, 2057
  - wait, 2058
  - wait\_for\_next\_used, 2059
- L4virtio::Driver::Virtio\_net\_device, 2060
  - bind\_rx\_notification\_irq, 2064
  - finish\_rx, 2064
  - rx\_pkt, 2064
  - rx\_queue\_size, 2065
  - setup\_device, 2065
  - tx, 2066
  - tx\_queue\_size, 2067
  - wait\_rx, 2068
- L4virtio::Driver::Virtio\_net\_device::Packet, 2069
- L4virtio::Driver::Virtqueue, 2070
  - alloc\_descriptor, 2074
  - desc, 2074
  - enqueue\_descriptor, 2074
  - find\_next\_used, 2075
  - free\_descriptor, 2075
  - init\_queue, 2076
  - initialize\_rings, 2077
- L4virtio::Ptr< T >, 2079
  - get, 2081
  - Invalid, 2080
  - Invalid\_type, 2080
  - is\_valid, 2081
- L4virtio::Svr::Bad\_descriptor, 2082
  - Bad\_address, 2083
  - Bad\_descriptor, 2083
  - Bad\_flags, 2083
  - Bad\_next, 2083
  - Bad\_rights, 2083
  - Bad\_size, 2083
  - Error, 2083
  - message, 2084
- L4virtio::Svr::Block\_dev\_base< Ds\_data >, 2084
  - Block\_dev\_base, 2088
  - finalize\_request, 2089
  - get\_writeback, 2090
  - set\_blk\_size, 2090
  - set\_config\_wce, 2090
  - set\_discard, 2091
  - set\_size\_max, 2091
  - set\_topology, 2091
  - set\_write\_zeroes, 2092
- L4virtio::Svr::Block\_request< Ds\_data >, 2093



- data\_size, [2094](#)
- next\_block, [2094](#)
- L4virtio::Svr::Console::Control\_message, [2095](#)
  - Console\_port, [2096](#)
  - Device\_add, [2096](#)
  - Device\_ready, [2096](#)
  - Device\_remove, [2096](#)
  - Events, [2096](#)
  - Port\_name, [2096](#)
  - Port\_open, [2096](#)
  - Port\_ready, [2096](#)
  - Resize, [2096](#)
- L4virtio::Svr::Console::Control\_request, [2097](#)
- L4virtio::Svr::Console::Device, [2098](#)
  - Device, [2103](#), [2104](#)
  - notify\_queue, [2105](#)
  - port, [2106](#)
  - port\_read, [2107](#)
  - port\_write, [2108](#)
  - process\_device\_ready, [2110](#)
  - process\_port\_open, [2111](#)
  - process\_port\_ready, [2111](#)
- L4virtio::Svr::Console::Device\_port, [2112](#)
- L4virtio::Svr::Console::Features, [2116](#)
  - console\_multiport\_bfm\_t, [2120](#)
  - console\_size\_bfm\_t, [2120](#)
  - emerg\_write\_bfm\_t, [2120](#)
- L4virtio::Svr::Console::Port, [2121](#)
  - Port\_added, [2124](#)
  - Port\_disabled, [2124](#)
  - Port\_failed, [2124](#)
  - Port\_num\_states, [2124](#)
  - Port\_open, [2124](#)
  - Port\_ready, [2124](#)
  - Port\_status, [2124](#)
  - state\_transitions, [2125](#)
- L4virtio::Svr::Console::Port::Transition, [2125](#)
- L4virtio::Svr::Console::Virtio\_con, [2126](#)
  - handle\_control\_message, [2132](#)
  - notify\_queue, [2132](#)
  - port, [2133](#)
  - port\_add, [2134](#)
  - port\_name, [2135](#)
  - port\_open, [2136](#)
  - port\_remove, [2137](#)
  - process\_device\_ready, [2138](#)
  - process\_port\_open, [2139](#)
  - process\_port\_ready, [2139](#)
  - reset\_device, [2140](#)
  - send\_control\_message, [2141](#)
  - Virtio\_con, [2131](#)
- L4virtio::Svr::Data\_buffer, [2143](#)
  - copy\_to, [2145](#)
  - Data\_buffer, [2144](#)
  - done, [2145](#)
  - set, [2146](#)
  - skip, [2146](#)
- L4virtio::Svr::Dev\_config, [2147](#)
- add\_irq\_status, [2151](#)
- change\_queue\_config, [2151](#)
- Dev\_config, [2149](#), [2150](#)
- ds, [2152](#)
- get\_cmd, [2152](#)
- guest\_features, [2153](#)
- hdr, [2153](#)
- negotiated\_features, [2154](#)
- qconfig, [2155](#)
- reset\_cmd, [2155](#)
- reset\_queue, [2156](#)
- set\_device\_needs\_reset, [2157](#)
- set\_device\_notify\_index, [2157](#)
- set\_status, [2158](#)
- status, [2158](#)
- L4virtio::Svr::Dev\_features, [2159](#)
- L4virtio::Svr::Dev\_status, [2162](#)
  - running, [2165](#)
- L4virtio::Svr::Device\_t< DATA >, [2165](#)
  - add\_trusted\_dataspaces, [2169](#)
  - device\_error, [2169](#)
  - device\_notify\_irq, [2169](#)
  - handle\_mem\_cmd\_write, [2169](#)
  - init\_mem\_info, [2170](#)
  - register\_driver\_irq, [2170](#)
  - reset\_queue\_config, [2170](#)
  - setup\_queue, [2171](#)
- L4virtio::Svr::Driver\_mem\_list\_t< DATA >, [2172](#)
  - add, [2174](#)
  - find, [2174](#)
  - full, [2175](#)
  - init, [2176](#)
  - load\_desc, [2176](#), [2177](#)
  - remove, [2178](#)
- L4virtio::Svr::Driver\_mem\_region\_t< DATA >, [2178](#)
  - contains, [2181](#)
  - Driver\_mem\_region\_t, [2181](#)
  - drv\_base, [2182](#)
  - ds, [2182](#)
  - ds\_offset, [2182](#)
  - empty, [2182](#)
  - flags, [2183](#)
  - is\_writable, [2183](#)
  - local, [2183](#)
  - local\_base, [2184](#)
  - size, [2184](#)
- L4virtio::Svr::Request\_processor, [2185](#)
  - current\_flags, [2186](#)
  - has\_more, [2187](#)
  - next, [2187](#)
  - start, [2189](#), [2191](#)
- L4virtio::Svr::Scmi::Base\_attr\_t, [2192](#)
- L4virtio::Svr::Scmi::Base\_proto, [2193](#)
- L4virtio::Svr::Scmi::Perf\_proto, [2195](#)
- L4virtio::Svr::Scmi::Performance\_attr\_t, [2198](#)
- L4virtio::Svr::Scmi::Performance\_describe\_level\_t, [2199](#)



- L4virtio::Svr::Scmi::Performance\_describe\_levels\_n\_t, 2199
- L4virtio::Svr::Scmi::Performance\_domain\_attr\_t, 2201
- L4virtio::Svr::Scmi::Proto< OBSERV >, 2203
- L4virtio::Svr::Scmi::Scmi\_dev, 2204
- L4virtio::Svr::Scmi::Scmi\_hdr\_t, 2208
- L4virtio::Svr::Virtio\_gpio< Request\_handler, Epiface >, 2210
- L4virtio::Svr::Virtio\_gpio< Request\_handler, Epiface >::Host\_irq, 2214
- L4virtio::Svr::Virtio\_gpio< Request\_handler, Epiface >::Irq\_handler, 2218
- L4virtio::Svr::Virtio\_gpio< Request\_handler, Epiface >::Request\_processor, 2219
  - get\_request, 2221
- L4virtio::Svr::Virtio\_i2c< Request\_handler, Epiface >, 2222
- L4virtio::Svr::Virtio\_i2c< Request\_handler, Epiface >::Host\_irq, 2226
- L4virtio::Svr::Virtio\_i2c< Request\_handler, Epiface >::Request\_processor, 2230
  - get\_request, 2232
- L4virtio::Svr::Virtio\_rng< Rnd\_state, Epiface >, 2233
- L4virtio::Svr::Virtio\_rng< Rnd\_state, Epiface >::Host\_irq, 2237
- L4virtio::Svr::Virtio\_rng< Rnd\_state, Epiface >::Request\_processor, 2241
- L4virtio::Svr::Virtio\_spi< Spi\_request\_handler, Epiface >, 2243
- L4virtio::Svr::Virtio\_spi< Spi\_request\_handler, Epiface >::Host\_irq, 2248
- L4virtio::Svr::Virtio\_spi< Spi\_request\_handler, Epiface >::Request\_processor, 2252
  - get\_request, 2254
- L4virtio::Svr::Virtqueue, 2255
  - consumed, 2259
  - desc, 2260
  - desc\_avail, 2261
  - disable\_notify, 2262
  - enable\_notify, 2262
  - finish, 2263, 2264
  - next\_avail, 2265
  - rewind\_avail, 2266
- L4virtio::Svr::Virtqueue::Head\_desc, 2267
  - desc, 2268
  - operator bool, 2268
  - valid, 2269
- L4virtio::Virtqueue, 2270
  - avail\_align, 2273
  - avail\_size, 2273
  - desc\_align, 2275
  - desc\_size, 2275
  - disable, 2276
  - dump, 2277
  - get\_avail\_idx, 2277
  - get\_tail\_avail\_idx, 2278
  - no\_notify\_guest, 2278
  - no\_notify\_host, 2279
  - num, 2279
  - ready, 2280
  - setup, 2281
  - setup\_simple, 2283
  - total\_size, 2283, 2284
  - used\_align, 2285
  - used\_size, 2285
- L4virtio::Virtqueue::Avail, 2287
- L4virtio::Virtqueue::Avail::Flags, 2288
  - no\_irq\_bfm\_t, 2289
- L4virtio::Virtqueue::Desc, 2289
- L4virtio::Virtqueue::Desc::Flags, 2291
  - indirect\_bfm\_t, 2292
  - next\_bfm\_t, 2292
  - write\_bfm\_t, 2293
- L4virtio::Virtqueue::Used, 2293
- L4virtio::Virtqueue::Used::Flags, 2294
  - no\_notify\_bfm\_t, 2295
- L4virtio::Virtqueue::Used\_elem, 2296
  - Used\_elem, 2297
- l4virtio\_block\_config\_t, 2297
- l4virtio\_block\_discard\_t, 2298
- l4virtio\_block\_header\_t, 2299
- L4virtio\_block\_operations
  - L4 VIRTIO Block Device, 485
  - L4VIRTIO\_BLOCK\_S\_IOERR
    - L4 VIRTIO Block Device, 485
  - L4VIRTIO\_BLOCK\_S\_OK
    - L4 VIRTIO Block Device, 485
  - L4VIRTIO\_BLOCK\_S\_UNSUPP
    - L4 VIRTIO Block Device, 485
- L4virtio\_block\_status
  - L4 VIRTIO Block Device, 485
- L4VIRTIO\_BLOCK\_T\_DISCARD
  - L4 VIRTIO Block Device, 485
- L4VIRTIO\_BLOCK\_T\_FLUSH
  - L4 VIRTIO Block Device, 485
- L4VIRTIO\_BLOCK\_T\_GET\_ID
  - L4 VIRTIO Block Device, 485
- L4VIRTIO\_BLOCK\_T\_IN
  - L4 VIRTIO Block Device, 485
- L4VIRTIO\_BLOCK\_T\_OUT
  - L4 VIRTIO Block Device, 485
- L4VIRTIO\_BLOCK\_T\_WRITE\_ZEROES
  - L4 VIRTIO Block Device, 485
- L4VIRTIO\_CMD\_CFG\_CHANGED
  - L4 VIRTIO Transport Layer, 478
- L4VIRTIO\_CMD\_CFG\_QUEUE
  - L4 VIRTIO Transport Layer, 478
- L4VIRTIO\_CMD\_MASK
  - L4 VIRTIO Transport Layer, 478
- L4VIRTIO\_CMD\_NONE
  - L4 VIRTIO Transport Layer, 478
- L4VIRTIO\_CMD\_NOTIFY\_QUEUE
  - L4 VIRTIO Transport Layer, 478
- L4VIRTIO\_CMD\_SET\_STATUS
  - L4 VIRTIO Transport Layer, 478
- l4virtio\_config\_hdr\_t, 2300

- l4virtio\_config\_queue
  - L4 VIRTIO Transport Layer, [480](#)
- l4virtio\_config\_queue\_t, [2301](#)
  - L4 VIRTIO Transport Layer, [477](#)
- l4virtio\_config\_queues
  - L4 VIRTIO Transport Layer, [481](#)
- l4virtio\_device\_config
  - L4 VIRTIO Transport Layer, [481](#)
- l4virtio\_device\_config\_ds
  - L4 VIRTIO Transport Layer, [481](#)
- L4virtio\_device\_ids
  - L4 VIRTIO Transport Layer, [479](#)
- l4virtio\_device\_notification\_irq
  - L4 VIRTIO Transport Layer, [482](#)
- L4virtio\_device\_status
  - L4 VIRTIO Transport Layer, [479](#)
- L4virtio\_feature\_bits
  - L4 VIRTIO Transport Layer, [480](#)
- L4VIRTIO\_FEATURE\_CMD\_CONFIG
  - L4 VIRTIO Transport Layer, [480](#)
- L4VIRTIO\_FEATURE\_VERSION\_1
  - L4 VIRTIO Transport Layer, [480](#)
- L4VIRTIO\_ID\_9P
  - L4 VIRTIO Transport Layer, [479](#)
- L4VIRTIO\_ID\_BALLOON
  - L4 VIRTIO Transport Layer, [479](#)
- L4VIRTIO\_ID\_BLOCK
  - L4 VIRTIO Transport Layer, [479](#)
- L4VIRTIO\_ID\_CAIF
  - L4 VIRTIO Transport Layer, [479](#)
- L4VIRTIO\_ID\_CAN
  - L4 VIRTIO Transport Layer, [479](#)
- L4VIRTIO\_ID\_CONSOLE
  - L4 VIRTIO Transport Layer, [479](#)
- L4VIRTIO\_ID\_CRYPTIO
  - L4 VIRTIO Transport Layer, [479](#)
- L4VIRTIO\_ID\_FS
  - L4 VIRTIO Transport Layer, [479](#)
- L4VIRTIO\_ID\_GPIO
  - L4 VIRTIO Transport Layer, [479](#)
- L4VIRTIO\_ID\_GPU
  - L4 VIRTIO Transport Layer, [479](#)
- L4VIRTIO\_ID\_I2C
  - L4 VIRTIO Transport Layer, [479](#)
- L4VIRTIO\_ID\_INPUT
  - L4 VIRTIO Transport Layer, [479](#)
- L4VIRTIO\_ID\_NET
  - L4 VIRTIO Transport Layer, [479](#)
- L4VIRTIO\_ID\_RNG
  - L4 VIRTIO Transport Layer, [479](#)
- L4VIRTIO\_ID\_RPMSG
  - L4 VIRTIO Transport Layer, [479](#)
- L4VIRTIO\_ID\_RPROC\_SERIAL
  - L4 VIRTIO Transport Layer, [479](#)
- L4VIRTIO\_ID\_SCSI
  - L4 VIRTIO Transport Layer, [479](#)
- L4VIRTIO\_ID\_SCSI
  - L4 VIRTIO Transport Layer, [479](#)
- L4VIRTIO\_ID\_SOCK
  - L4 VIRTIO Transport Layer, [479](#)
- L4VIRTIO\_ID\_SPI
  - L4 VIRTIO Transport Layer, [479](#)
- L4VIRTIO\_ID\_VSOCK
  - L4 VIRTIO Transport Layer, [479](#)
- L4VIRTIO\_ID\_WATCHDOG
  - L4 VIRTIO Transport Layer, [479](#)
- l4virtio\_input\_absinfo\_t, [2302](#)
- l4virtio\_input\_config\_t, [2303](#)
- l4virtio\_input\_devids\_t, [2303](#)
- l4virtio\_input\_event\_t, [2304](#)
- L4VIRTIO\_IRQ\_STATUS\_CONFIG
  - L4 VIRTIO Transport Layer, [478](#)
- L4VIRTIO\_IRQ\_STATUS\_VRING
  - L4 VIRTIO Transport Layer, [478](#)
- l4virtio\_net\_config\_t, [2305](#)
- l4virtio\_net\_header\_t, [2305](#)
- L4VIRTIO\_OP\_CONFIG\_QUEUE
  - L4 VIRTIO Transport Layer, [479](#)
- L4VIRTIO\_OP\_DEVICE\_CONFIG
  - L4 VIRTIO Transport Layer, [479](#)
- L4VIRTIO\_OP\_GET\_DEVICE\_IRQ
  - L4 VIRTIO Transport Layer, [479](#)
- L4VIRTIO\_OP\_REGISTER\_DS
  - L4 VIRTIO Transport Layer, [479](#)
- L4VIRTIO\_OP\_SET\_STATUS
  - L4 VIRTIO Transport Layer, [478](#)
- L4virtio\_port, [2306](#)
  - drop\_requests, [2311](#)
- l4virtio\_register\_ds
  - L4 VIRTIO Transport Layer, [482](#)
- l4virtio\_set\_status
  - L4 VIRTIO Transport Layer, [483](#)
- L4VIRTIO\_STATUS\_ACKNOWLEDGE
  - L4 VIRTIO Transport Layer, [480](#)
- L4VIRTIO\_STATUS\_DEVICE\_NEEDS\_RESET
  - L4 VIRTIO Transport Layer, [480](#)
- L4VIRTIO\_STATUS\_DRIVER
  - L4 VIRTIO Transport Layer, [480](#)
- L4VIRTIO\_STATUS\_DRIVER\_OK
  - L4 VIRTIO Transport Layer, [480](#)
- L4VIRTIO\_STATUS\_FAILED
  - L4 VIRTIO Transport Layer, [480](#)
- L4VIRTIO\_STATUS\_FEATURES\_OK
  - L4 VIRTIO Transport Layer, [480](#)
- Last
  - L4::lpc::Snd\_fpage, [1187](#)
- lcm
  - cxx, [727](#)
- learn
  - Mac\_table< Size >, [2314](#)
- length
  - L4::lpc::Varg, [1198](#)
- Libedid\_block\_size
  - EDID parsing functionality, [447](#)
- libedid\_check\_header
  - EDID parsing functionality, [447](#)

- libedid\_checksum
  - EDID parsing functionality, [447](#)
- Libedid\_consts
  - EDID parsing functionality, [446](#)
- libedid\_dump
  - EDID parsing functionality, [447](#)
- libedid\_dump\_standard\_timings
  - EDID parsing functionality, [448](#)
- libedid\_num\_ext\_blocks
  - EDID parsing functionality, [448](#)
- libedid\_pnp\_id
  - EDID parsing functionality, [448](#)
- libedid\_prefered\_resolution
  - EDID parsing functionality, [449](#)
- libedid\_revision
  - EDID parsing functionality, [449](#)
- libedid\_version
  - EDID parsing functionality, [449](#)
- Link
  - L4Re::Namespace, [1700](#)
- link
  - L4Re::Vfs::Directory, [1850](#)
- List\_alloc
  - cxx::List\_alloc, [910](#)
- list\_alloc.h
  - l4la\_alloc, [3353](#)
  - l4la\_avail, [3353](#)
  - l4la\_dump, [3353](#)
  - l4la\_free, [3354](#)
  - l4la\_init, [3354](#)
- load\_desc
  - L4virtio::Svr::Driver\_mem\_list\_t< DATA >, [2176](#), [2177](#)
- local
  - L4virtio::Svr::Driver\_mem\_region\_t< DATA >, [2183](#)
- local\_base
  - L4virtio::Svr::Driver\_mem\_region\_t< DATA >, [2184](#)
- local\_id\_received
  - L4::lpc::Snd\_fpage, [1190](#)
- Lock\_guard
  - L4::Lock\_guard, [1307](#)
- log
  - L4Re::Env, [1640](#)
- Log interface, [532](#)
  - l4re\_log\_print, [533](#)
  - l4re\_log\_print\_srv, [533](#)
  - l4re\_log\_printn, [534](#)
  - l4re\_log\_printn\_srv, [534](#)
- Logging interface, [586](#)
- lookup
  - Mac\_table< Size >, [2314](#)
- loop
  - L4::Server< LOOP\_HOOKS >, [1371](#)
  - L4Re::Util::Registry\_server< LOOP\_HOOKS >, [1831](#)
- loop\_dbg
  - L4::Server< LOOP\_HOOKS >, [1371](#)
  - L4Re::Util::Registry\_server< LOOP\_HOOKS >, [1832](#)
- Low-Level Thread Functions, [713](#)
- lower\_bound\_node
  - cxx::Bits::Base\_avl\_set< ITEM\_TYPE, COMPARE, ALLOC, GET\_KEY >, [861](#)
  - cxx::Bits::Bst< Node, Get\_key, Compare >, [877](#)
- Lsb
  - cxx::Bitfield< T, LSB, MSB >, [821](#)
- lseek
  - L4Re::Vfs::Regular\_file, [1883](#)
- Lstr
  - L4::Factory::Lstr, [1067](#)
- Mac\_addr, [2312](#)
- Mac\_table< Size >, [2312](#)
  - flush, [2314](#)
  - learn, [2314](#)
  - lookup, [2314](#)
- Mag, the GUI Multiplexer, [82](#)
- main\_thread
  - L4Re::Env, [1641](#)
- make\_cap
  - L4::lpc, [746](#)
- make\_cap\_full
  - L4::lpc, [747](#)
- make\_cap\_rw
  - L4::lpc, [747](#)
- make\_cap\_rws
  - L4::lpc, [748](#)
- make\_ref\_cap
  - L4Re Capability API, [578](#)
- make\_ref\_del\_cap
  - L4Re Capability API, [578](#)
- make\_shared\_cap
  - L4Re, [770](#)
  - L4Re::Util, [780](#)
- make\_shared\_del\_cap
  - L4Re, [771](#)
  - L4Re::Util, [781](#)
- make\_unique\_cap
  - L4Re, [772](#)
  - L4Re::Util, [781](#)
- make\_unique\_del\_cap
  - L4Re, [772](#)
  - L4Re::Util, [781](#)
- Map
  - L4::lpc::Snd\_fpage, [1187](#)
- map
  - L4::Task, [1399](#)
  - L4Re::Dataspace, [1610](#)
  - L4Re::Dma\_space, [1627](#)
  - L4Re::Util::Dataspace\_svr, [1791](#)
- map\_hook
  - L4Re::Util::Dataspace\_svr, [1792](#)
- map\_info
  - L4Re::Dataspace, [1612](#)
  - L4Re::Util::Dataspace\_svr, [1793](#)

- map\_region
  - L4Re::Dataspace, [1613](#)
- Map\_type
  - L4::lpc::Snd\_fpage, [1187](#)
- mask
  - L4::lcu, [1081](#)
- max
  - Small C++ Template Library, [630](#), [631](#)
- max\_free\_slabs
  - cxx::Base\_slab< Obj\_size, Slab\_size, Max\_free, Alloc >, [811](#)
  - cxx::Base\_slab\_static< Obj\_size, Slab\_size, Max\_free, Alloc >, [816](#)
- max\_queue\_size
  - L4virtio::Driver::Device, [2054](#)
- MB\_ART\_MEMORY
  - mb\_info.h, [3360](#)
- mb\_info.h
  - l4util\_mb\_for\_each\_mmap\_entry, [3360](#)
  - L4UTIL\_MB\_MEMORY, [3360](#)
  - MB\_ART\_MEMORY, [3360](#)
- Mem
  - L4::Type\_info::Demand\_t< CAPS, FLAGS, MEM, PORTS >, [1443](#)
- mem
  - L4::lpc::Rcv\_fpage, [1176](#)
  - L4::lpc::Snd\_fpage, [1190](#)
- mem\_alloc
  - L4Re::Env, [1641](#)
- Mem\_alloc\_flags
  - L4Re::Mem\_alloc, [1685](#)
- Mem\_desc
  - L4::Kip::Mem\_desc, [1277](#)
- mem\_free
  - L4Re::Mem\_alloc::Stats, [1688](#)
- mem\_limit
  - L4Re::Mem\_alloc::Stats, [1688](#)
- Mem\_type
  - L4::Kip::Mem\_desc, [1276](#)
- mem\_used
  - L4Re::Mem\_alloc::Stats, [1688](#)
- Memory
  - L4::lpc::Gen\_fpage, [1116](#)
- Memory allocator, [535](#)
  - l4re\_ma\_alloc, [536](#)
  - l4re\_ma\_alloc\_align, [537](#)
  - l4re\_ma\_alloc\_align\_srv, [539](#)
  - l4re\_ma\_flags, [536](#)
- Memory descriptors (C version), [432](#)
  - l4\_kernel\_info\_get\_mem\_desc\_end, [435](#)
  - l4\_kernel\_info\_get\_mem\_desc\_is\_virtual, [435](#)
  - l4\_kernel\_info\_get\_mem\_desc\_start, [435](#)
  - l4\_kernel\_info\_get\_mem\_desc\_subtype, [435](#)
  - l4\_kernel\_info\_get\_mem\_desc\_type, [436](#)
  - l4\_kernel\_info\_get\_num\_mem\_descs, [436](#)
  - l4\_kernel\_info\_mem\_desc\_t, [433](#)
  - l4\_kernel\_info\_set\_mem\_desc, [436](#)
  - l4\_mem\_archspecific\_acpi\_nvs, [434](#)
  - l4\_mem\_archspecific\_acpi\_tables, [434](#)
  - l4\_mem\_archspecific\_sub\_type\_common\_t, [434](#)
  - l4\_mem\_info\_acpi\_rsdp, [434](#)
  - l4\_mem\_info\_sub\_type\_t, [434](#)
  - l4\_mem\_reserved\_heap, [434](#)
  - l4\_mem\_reserved\_kernel, [434](#)
  - l4\_mem\_reserved\_mmio, [434](#)
  - l4\_mem\_type\_archspecific, [435](#)
  - l4\_mem\_type\_bootloader, [434](#)
  - l4\_mem\_type\_conventional, [434](#)
  - l4\_mem\_type\_dedicated, [434](#)
  - l4\_mem\_type\_info, [434](#)
  - l4\_mem\_type\_reserved, [434](#)
  - l4\_mem\_type\_shared, [434](#)
  - l4\_mem\_type\_t, [434](#)
  - l4\_mem\_type\_undefined, [434](#)
- Memory management - Data Spaces and the Region Map, [27](#)
- Memory Operations, [441](#)
  - l4\_mem\_op\_widths, [442](#)
  - l4\_mem\_read, [443](#)
  - L4\_MEM\_WIDTH\_1BYTE, [442](#)
  - L4\_MEM\_WIDTH\_2BYTE, [442](#)
  - L4\_MEM\_WIDTH\_4BYTE, [442](#)
  - l4\_mem\_write, [443](#)
- Memory related, [196](#)
  - l4\_addr\_consts\_t, [200](#)
  - l4\_bytes\_to\_mwords, [201](#)
  - L4\_INVALID\_ADDR, [201](#)
  - L4\_LOG2\_PAGESIZE, [198](#)
  - L4\_LOG2\_SUPERPAGESIZE, [198](#)
  - L4\_PAGEMASK, [198](#)
  - L4\_PAGESHIFT, [198](#), [199](#)
  - l4\_round\_page, [201](#)
  - l4\_round\_size, [202](#)
  - L4\_SUPERPAGEMASK, [199](#)
  - L4\_SUPERPAGESHIFT, [199](#), [200](#)
  - L4\_SUPERPAGESIZE, [200](#)
  - l4\_trunc\_page, [203](#)
  - l4\_trunc\_size, [204](#)
- message
  - L4virtio::Svr::Bad\_descriptor, [2084](#)
- Message Items, [225](#)
  - L4\_FPAGE\_BUFFERABLE, [227](#)
  - L4\_FPAGE\_CACHE\_OPT, [227](#)
  - l4\_fpage\_cacheability\_opt\_t, [227](#)
  - L4\_FPAGE\_CACHEABLE, [227](#)
  - L4\_FPAGE\_UNCACHEABLE, [227](#)
  - L4\_ITEM\_CONT, [227](#)
  - L4\_ITEM\_MAP, [227](#)
  - l4\_map\_control, [229](#)
  - L4\_MAP\_ITEM\_GRANT, [228](#)
  - L4\_MAP\_ITEM\_MAP, [228](#)
  - l4\_map\_obj\_control, [230](#)
  - l4\_msg\_item\_consts\_t, [227](#)
  - L4\_RCV\_ITEM\_FORWARD\_MAPPINGS, [228](#)
  - L4\_RCV\_ITEM\_LOCAL\_ID, [229](#)
  - L4\_RCV\_ITEM\_SINGLE\_CAP, [228](#)

- Message Registers (MRs), [265](#)
- Message Tag, [247](#)
  - l4\_msgtag, [250](#)
  - L4\_MSGTAG\_ERROR, [249](#)
  - L4\_MSGTAG\_FLAGS, [249](#)
  - L4\_msgtag\_flags, [249](#)
  - l4\_msgtag\_flags, [252](#)
  - l4\_msgtag\_has\_error, [253](#)
  - l4\_msgtag\_is\_exception, [254](#)
  - l4\_msgtag\_is\_io\_page\_fault, [255](#)
  - l4\_msgtag\_is\_page\_fault, [256](#)
  - l4\_msgtag\_is\_sigma0, [257](#)
  - l4\_msgtag\_items, [257](#)
  - l4\_msgtag\_label, [258](#)
  - L4\_msgtag\_protocol, [249](#)
  - L4\_MSGTAG\_SCHEDULE, [249](#)
  - L4\_MSGTAG\_TRANSFER\_FPU, [249](#)
  - l4\_msgtag\_words, [259](#)
  - L4\_platform\_ctl\_proto, [250](#)
  - L4\_PROTO\_ALLOW\_SYSCALL, [249](#)
  - L4\_PROTO\_DEBUGGER, [250](#)
  - L4\_PROTO\_DMA\_SPACE, [250](#)
  - L4\_PROTO\_EXCEPTION, [250](#)
  - L4\_PROTO\_FACTORY, [250](#)
  - L4\_PROTO\_IO\_PAGE\_FAULT, [250](#)
  - L4\_PROTO\_IOMMU, [250](#)
  - L4\_PROTO\_IRQ, [249](#)
  - L4\_PROTO\_IRQ\_SENDER, [250](#)
  - L4\_PROTO\_KOBJECT, [250](#)
  - L4\_PROTO\_LOG, [250](#)
  - L4\_PROTO\_META, [250](#)
  - L4\_PROTO\_NONE, [249](#)
  - L4\_PROTO\_PAGE\_FAULT, [249](#)
  - L4\_PROTO\_PF\_EXCEPTION, [249](#)
  - L4\_PROTO\_PLATFORM\_CTL, [250](#)
  - L4\_PROTO\_SCHEDULER, [250](#)
  - L4\_PROTO\_SEMAPHORE, [250](#)
  - L4\_PROTO\_SIGMA0, [250](#)
  - L4\_PROTO\_SMCCC, [250](#)
  - L4\_PROTO\_TASK, [250](#)
  - L4\_PROTO\_THREAD, [250](#)
  - L4\_PROTO\_THREAD\_GROUP, [250](#)
  - L4\_PROTO\_VCPU\_CONTEXT, [250](#)
  - L4\_PROTO\_VM, [250](#)
- min
  - Small C++ Template Library, [631](#), [632](#)
- mkdir
  - L4Re::Vfs::Directory, [1850](#)
- mmio\_read
  - L4Re::Mmio\_space, [1693](#)
- mmio\_write
  - L4Re::Mmio\_space, [1694](#)
- Mode
  - L4Re::Util::Event\_t< PAYLOAD >, [1806](#)
- mode
  - L4::Uart, [1503](#)
- Mode\_irq
  - L4Re::Util::Event\_t< PAYLOAD >, [1806](#)
- Mode\_polling
  - L4Re::Util::Event\_t< PAYLOAD >, [1806](#)
- modify
  - L4drivers::Register\_tmpl< BITS, BLOCK >, [1583](#)
- modify\_senders
  - L4::Thread, [1410](#)
- Moe, [51](#)
- More
  - L4::lpc::Snd\_fpage, [1187](#)
- mount
  - L4Re::Vfs::File\_system, [1858](#)
  - L4Re::Vfs::Fs, [1863](#)
- move
  - L4::Cap< T >, [1008](#)
  - L4::Cap\_base, [1017](#)
- Mr\_bytes
  - L4::lpc::Msg, [752](#)
- Mr\_words
  - L4::lpc::Msg, [752](#)
- Msb
  - cxx::Bitfield< T, LSB, MSB >, [821](#)
- msg\_add
  - L4::lpc::Msg, [755](#)
- msg\_get
  - L4::lpc::Msg, [756](#)
- Msg\_ptr
  - L4::lpc::Msg\_ptr< T >, [1163](#)
- msg\_ptr
  - L4::lpc, [749](#)
- msi\_info
  - L4::lcu, [1082](#)
- N
  - cxx::Bits::Direction, [885](#)
- Name-space API, [586](#)
- Name\_max
  - L4Re::Inhibitor, [1662](#)
- Namespace interface, [540](#)
  - l4re\_ns\_query\_srv, [541](#)
  - l4re\_ns\_query\_to\_srv, [542](#)
  - l4re\_ns\_register\_flags, [541](#)
  - l4re\_ns\_register\_obj\_srv, [543](#)
- Ned, the Init Process, [56](#)
- negotiated\_features
  - L4virtio::Svr::Dev\_config, [2154](#)
- Net\_transfer, [2315](#)
  - cur\_buf, [2317](#)
  - done, [2317](#)
- new\_sched
  - vmm.lua, [2396](#)
- next
  - L4Re::Event\_buffer\_t< PAYLOAD >, [1657](#)
  - L4virtio::Svr::Request\_processor, [2187](#)
- next\_avail
  - L4virtio::Svr::Virtqueue, [2265](#)
- next\_bfm\_t
  - L4virtio::Virtqueue::Desc::Flags, [2292](#)
- next\_block
  - L4virtio::Svr::Block\_request< Ds\_data >, [2094](#)

- next\_device
  - L4vbus::Device, [1964](#)
- next\_lock\_info
  - L4Re::Inhibitor, [1663](#)
- next\_timeout
  - L4::lpc\_svr::Timeout\_queue, [1245](#)
- no\_demand
  - L4::Type\_info::Demand, [1439](#)
- No\_eager\_map
  - L4Re::Rm::F, [1738](#)
  - Rm::F, [2334](#)
- No\_init
  - L4::Cap\_base, [1011](#)
- No\_init\_type
  - L4::Cap\_base, [1011](#)
- no\_irq\_bfm\_t
  - L4virtio::Virtqueue::Avail::Flags, [2289](#)
- no\_notify\_bfm\_t
  - L4virtio::Virtqueue::Used::Flags, [2295](#)
- no\_notify\_guest
  - L4virtio::Virtqueue, [2278](#)
- no\_notify\_host
  - L4virtio::Virtqueue, [2279](#)
- No\_sync
  - L4Re::Dma\_space, [1625](#)
- None
  - L4::lpc::Snd\_fpage, [1186](#)
  - L4::Types::Flags< BITS\_ENUM, UNDERLYING >, [1479](#)
  - L4Re::Dma\_space, [1625](#)
- None\_type
  - L4::Types::Flags< BITS\_ENUM, UNDERLYING >, [1479](#)
- Normal
  - L4Re::Dataspace::F, [1616](#)
- notify\_queue
  - L4virtio::Svr::Console::Device, [2105](#)
  - L4virtio::Svr::Console::Virtio\_con, [2132](#)
  - Virtio\_net, [2350](#)
- NT\_ASRS
  - ELF binary format, [699](#)
- NT\_AUXV
  - ELF binary format, [699](#)
- NT\_FPREGSET
  - ELF binary format, [699](#)
- NT\_GWINDOWS
  - ELF binary format, [699](#)
- NT\_LWPSINFO
  - ELF binary format, [700](#)
- NT\_LWPSTATUS
  - ELF binary format, [700](#)
- NT\_PLATFORM
  - ELF binary format, [699](#)
- NT\_PRURED
  - ELF binary format, [700](#)
- NT\_PRFPXREG
  - ELF binary format, [700](#)
- NT\_PRPSINFO
  - ELF binary format, [699](#)
- NT\_PRSTATUS
  - ELF binary format, [699](#)
- NT\_PRXREG
  - ELF binary format, [699](#)
- NT\_PSINFO
  - ELF binary format, [699](#)
- NT\_PSTATUS
  - ELF binary format, [699](#)
- NT\_TASKSTRUCT
  - ELF binary format, [699](#)
- NT\_UTSNAME
  - ELF binary format, [700](#)
- NT\_VERSION
  - ELF binary format, [700](#)
- num
  - L4virtio::Virtqueue, [2279](#)
- num\_interfaces
  - L4::Meta, [1313](#)
- Obj
  - L4::lpc::Gen\_fpage, [1116](#)
- obj
  - L4::lpc::Rcv\_fpage, [1177](#)
  - L4::lpc::Snd\_fpage, [1191](#)
- obj\_cap
  - L4::Epiface, [1043](#)
  - L4::Epiface\_t0< RPC\_IFACE, BASE >, [1052](#)
  - L4::lrqep\_t< Derived, BASE, bool >, [1272](#)
- obj\_info.h
  - l4\_debugger\_query\_obj\_infos, [3217](#)
- Object Invocation, [207](#)
- l4\_ipc, [210](#)
- l4\_ipc\_call, [211](#)
- l4\_ipc\_receive, [214](#)
- l4\_ipc\_reply\_and\_wait, [216](#)
- l4\_ipc\_send, [217](#)
- l4\_ipc\_send\_and\_wait, [219](#)
- l4\_ipc\_sleep, [220](#)
- l4\_ipc\_sleep\_ms, [221](#)
- l4\_ipc\_sleep\_us, [222](#)
- l4\_ipc\_wait, [223](#)
- l4\_sndfpage\_add, [224](#)
- L4\_SYSF\_NONE, [209](#)
- Object\_registry
  - L4Re::Util::Object\_registry, [1820](#)
- object\_size
  - cxx::Base\_slab< Obj\_size, Slab\_size, Max\_free, Alloc >, [811](#)
  - cxx::Base\_slab\_static< Obj\_size, Slab\_size, Max\_free, Alloc >, [816](#)
- objects\_per\_slab
  - cxx::Base\_slab< Obj\_size, Slab\_size, Max\_free, Alloc >, [811](#)
  - cxx::Base\_slab\_static< Obj\_size, Slab\_size, Max\_free, Alloc >, [816](#)
- offset
  - l4\_sched\_cpu\_set\_t, [1541](#)
- op\_create

- Switch\_factory, [2345](#)
- operator bool
  - L4virtio::Svr::Virtqueue::Head\_desc, [2268](#)
- operator l4\_msgtag\_t
  - L4::Factory::S, [1071](#)
- operator new
  - Small C++ Template Library, [632](#)
- operator value\_type
  - L4drivers::Ro\_register\_tmpl< BITS, BLOCK >, [1590](#)
- operator!
  - cxx::Bits::Direction, [886](#)
- operator!=
  - L4vbus::Device, [1964](#)
- operator<<
  - ipc\_stream, [2619–2621](#)
  - L4::Factory::S, [1071](#), [1072](#)
- operator>>
  - ipc\_stream, [2621–2625](#)
- operator()
  - cxx::Pair\_first\_compare< Cmp, Typ >, [927](#)
- operator->
  - cxx::Bits::Avl\_set\_iter< Node, Key, Node\_op >, [853](#)
  - cxx::Bits::Base\_avl\_set< ITEM\_TYPE, COMPARE, ALLOC, GET\_KEY >::Node, [865](#)
- operator=
  - cxx::Bits::Base\_avl\_set< ITEM\_TYPE, COMPARE, ALLOC, GET\_KEY >, [862](#)
  - L4::Lock\_guard, [1308](#)
  - L4drivers::Register\_tmpl< BITS, BLOCK >, [1584](#)
  - L4Re::Rm::Unique\_region< T >, [1744](#)
  - Rm::Unique\_region< T >, [2340](#)
- operator==
  - L4Re::Video::Color\_component, [1892](#)
  - L4Re::Video::Pixel\_info, [1915](#)
  - L4vbus::Device, [1965](#)
- operator[]
  - cxx::Avl\_map< KEY\_TYPE, DATA\_TYPE, COMPARE, ALLOC >, [793](#), [794](#)
  - cxx::Bitmap\_base, [842](#), [843](#)
  - cxx::List< D, Alloc >, [907](#)
  - L4drivers::Register\_block< MAX\_BITS, BLOCK >, [1573](#), [1574](#)
  - L4drivers::Ro\_register\_block< MAX\_BITS, BLOCK >, [1587](#)
  - L4Re::Util::Bitmap\_base, [1761](#), [1762](#)
- operator\*
  - cxx::Bits::Avl\_set\_iter< Node, Key, Node\_op >, [853](#)
  - cxx::Bits::Base\_avl\_set< ITEM\_TYPE, COMPARE, ALLOC, GET\_KEY >::Node, [865](#)
- Overview, [1](#)
- Overwrite
  - L4Re::Namespace, [1700](#)
- p\_flags
  - Elf32\_Phdr, [970](#)
  - Elf64\_Phdr, [980](#)
- p\_type
  - Elf32\_Phdr, [970](#)
  - Elf64\_Phdr, [980](#)
- padding
  - L4Re::Video::Pixel\_info, [1916](#)
- page\_fault
  - L4::Pager, [1321](#)
- page\_shift
  - L4Re::Util::Dataspace\_svr, [1793](#)
- Pager
  - L4Re::Rm::F, [1739](#)
  - Rm::F, [2334](#)
- pager
  - L4::Thread::Attr, [1423](#)
- Pair
  - cxx::Pair< First, Second >, [925](#)
- Pair\_first\_compare
  - cxx::Pair\_first\_compare< Cmp, Typ >, [926](#)
- parent
  - L4Re::Env, [1642](#)
- Parent API, [587](#)
- Parent interface, [544](#)
- parent.h
  - l4re\_parent\_signal, [2828](#)
- parse\_cmdline
  - Comfortable Command Line Parsing, [710](#)
- Partly\_resolved
  - L4Re::Namespace, [1699](#)
- PF\_ARM\_SB
  - ELF binary format, [691](#)
- PF\_MASKOS
  - ELF binary format, [701](#)
- PF\_MASKPROC
  - ELF binary format, [701](#)
- PF\_R
  - ELF binary format, [701](#)
- PF\_W
  - ELF binary format, [701](#)
- PF\_X
  - ELF binary format, [701](#)
- Phys\_space
  - L4Re::Dma\_space, [1625](#)
- pin
  - L4vbus::Gpio\_module, [1970](#)
  - L4vbus::Gpio\_pin, [1979](#)
- Pinned
  - L4Re::Mem\_alloc, [1685](#)
- Pixel\_info
  - L4Re::Video::Pixel\_info, [1909](#), [1910](#)
- pkg/drivers-frst/include/ARCH-amd64/asm\_access.h, [2363](#)
- pkg/drivers-frst/include/ARCH-arm/asm\_access.h, [2364](#)
- pkg/drivers-frst/include/ARCH-arm64/asm\_access.h, [2365](#)
- pkg/drivers-frst/include/ARCH-mips/asm\_access.h, [2366](#)
- pkg/drivers-frst/include/ARCH-ppc32/asm\_access.h, [2366](#)



- pkg/drivers-frst/include/ARCH-riscv/asm\_access.h, 2366
- pkg/drivers-frst/include/ARCH-sparc/asm\_access.h, 2367
- pkg/drivers-frst/include/ARCH-x86/asm\_access.h, 2368
- pkg/drivers-frst/include/asm\_access\_gen.h, 2368
- pkg/drivers-frst/include/hw\_mmio\_register\_block, 2369
- pkg/drivers-frst/include/hw\_register\_block, 2370
- pkg/drivers-frst/include/io\_regblock.h, 2373
- pkg/drivers-frst/include/io\_regblock\_port.h, 2375
- pkg/drivers-frst/include/Makefile, 2419
- pkg/drivers-frst/include/poll\_timeout\_counter.h, 2376
- pkg/drivers-frst/uart/include/device.h, 2377
- pkg/drivers-frst/uart/include/Makefile, 2419
- pkg/drivers-frst/uart/include/uart\_16550.h, 2378
- pkg/drivers-frst/uart/include/uart\_16550\_dw.h, 2379
- pkg/drivers-frst/uart/include/uart\_apb.h, 2380
- pkg/drivers-frst/uart/include/uart\_base.h, 2380
- pkg/drivers-frst/uart/include/uart\_cadence.h, 2382
- pkg/drivers-frst/uart/include/uart\_dcc-v6.h, 2382
- pkg/drivers-frst/uart/include/uart\_dm.h, 2383
- pkg/drivers-frst/uart/include/uart\_dummy.h, 2383
- pkg/drivers-frst/uart/include/uart\_geni.h, 2384
- pkg/drivers-frst/uart/include/uart\_imx.h, 2384
- pkg/drivers-frst/uart/include/uart\_leon3.h, 2385
- pkg/drivers-frst/uart/include/uart\_linflex.h, 2386
- pkg/drivers-frst/uart/include/uart\_lpuart.h, 2386
- pkg/drivers-frst/uart/include/uart\_mvebu.h, 2387
- pkg/drivers-frst/uart/include/uart\_of.h, 2387
- pkg/drivers-frst/uart/include/uart\_omap35x.h, 2388
- pkg/drivers-frst/uart/include/uart\_pl011.h, 2388
- pkg/drivers-frst/uart/include/uart\_s3c2410.h, 2389
- pkg/drivers-frst/uart/include/uart\_sa1000.h, 2390
- pkg/drivers-frst/uart/include/uart\_sbi.h, 2391
- pkg/drivers-frst/uart/include/uart\_sh.h, 2391
- pkg/drivers-frst/uart/include/uart\_sifive.h, 2392
- pkg/drivers-frst/uart/include/uart\_tegra-tcu.h, 2392
- pkg/l4re-core/ned/doc/tutorial.lua, 2393
- pkg/l4re-core/ned/lib/include/cmd\_control, 2395
- pkg/l4re-core/ned/lib/include/Makefile, 2419
- pkg/uvmm/configs/vmm.lua, 2396, 2400
- pkg/virtio-net-switch/server/switch/debug.h, 2404
- pkg/virtio-net-switch/server/switch/filter.cc, 2407
- pkg/virtio-net-switch/server/switch/filter.h, 2407
- pkg/virtio-net-switch/server/switch/mac\_addr.h, 2408
- pkg/virtio-net-switch/server/switch/mac\_table.h, 2409
- pkg/virtio-net-switch/server/switch/main.cc, 2410
- pkg/virtio-net-switch/server/switch/Makefile, 2419
- pkg/virtio-net-switch/server/switch/options.cc, 2419
- pkg/virtio-net-switch/server/switch/options.h, 2422
- pkg/virtio-net-switch/server/switch/port.h, 2422
- pkg/virtio-net-switch/server/switch/port\_ixl.h, 2425
- pkg/virtio-net-switch/server/switch/port\_l4virtio.h, 2427
- pkg/virtio-net-switch/server/switch/request.h, 2430
- pkg/virtio-net-switch/server/switch/request\_ixl.h, 2432
- pkg/virtio-net-switch/server/switch/request\_l4virtio.h, 2433
- pkg/virtio-net-switch/server/switch/stats.h, 2436
- pkg/virtio-net-switch/server/switch/switch.cc, 2437
- pkg/virtio-net-switch/server/switch/switch.h, 2440
- pkg/virtio-net-switch/server/switch/virtio\_net.h, 2441
- pkg/virtio-net-switch/server/switch/virtio\_net\_buffer.h, 2445
- pkg/virtio-net-switch/server/switch/vlan.h, 2446
- Platform Control C API, 346
  - l4\_platform\_ctl\_cpu\_allow\_shutdown, 347
  - l4\_platform\_ctl\_cpu\_disable, 348
  - l4\_platform\_ctl\_cpu\_enable, 348
  - l4\_platform\_ctl\_set\_task\_asid, 349
  - l4\_platform\_ctl\_system\_shutdown, 350
  - l4\_platform\_ctl\_system\_suspend, 351
- pm\_resume
  - L4vbus::Pm< DEC >, 2000
- pm\_suspend
  - L4vbus::Pm< DEC >, 2000
- Poll\_timeout\_counter
  - L4::Poll\_timeout\_counter, 1332
- Poll\_timeout\_kipclock
  - L4::Poll\_timeout\_kipclock, 1334
- pop\_front
  - cxx::Bits::Smart\_ptr\_list< ITEM >, 889
  - cxx::H\_list< T, POLICY >, 897
  - cxx::S\_list< T, POLICY >, 937
- port
  - L4virtio::Svr::Console::Device, 2106
  - L4virtio::Svr::Console::Virtio\_con, 2133
- port\_add
  - L4virtio::Svr::Console::Virtio\_con, 2134
- Port\_added
  - L4virtio::Svr::Console::Port, 2124
- port\_available
  - Virtio\_switch, 2357
- Port\_disabled
  - L4virtio::Svr::Console::Port, 2124
- Port\_failed
  - L4virtio::Svr::Console::Port, 2124
- Port\_name
  - L4virtio::Svr::Console::Control\_message, 2096
- port\_name
  - L4virtio::Svr::Console::Virtio\_con, 2135
- Port\_num\_states
  - L4virtio::Svr::Console::Port, 2124
- Port\_open
  - L4virtio::Svr::Console::Control\_message, 2096
  - L4virtio::Svr::Console::Port, 2124
- port\_open
  - L4virtio::Svr::Console::Virtio\_con, 2136
- port\_read
  - L4virtio::Svr::Console::Device, 2107
- Port\_ready
  - L4virtio::Svr::Console::Control\_message, 2096
  - L4virtio::Svr::Console::Port, 2124
- port\_remove
  - L4virtio::Svr::Console::Virtio\_con, 2137
- Port\_status
  - L4virtio::Svr::Console::Port, 2124



- port\_write
  - L4virtio::Svr::Console::Device, [2108](#)
- Ports
  - L4::Type\_info::Demand\_t< CAPS, FLAGS, MEM, PORTS >, [1443](#)
- print
  - L4Re::Log, [1680](#)
- println
  - L4Re::Log, [1680](#)
- prio
  - l4\_sched\_param\_t, [1545](#)
- process
  - L4Re::Util::Event\_buffer\_consumer\_t< PAYLOAD >, [1797](#)
- process\_device\_ready
  - L4virtio::Svr::Console::Device, [2110](#)
  - L4virtio::Svr::Console::Virtio\_con, [2138](#)
- process\_port\_open
  - L4virtio::Svr::Console::Device, [2111](#)
  - L4virtio::Svr::Console::Virtio\_con, [2139](#)
- process\_port\_ready
  - L4virtio::Svr::Console::Device, [2111](#)
  - L4virtio::Svr::Console::Virtio\_con, [2139](#)
- process\_request
  - L4virtio::Driver::Block\_device, [2042](#)
- process\_used\_queue
  - L4virtio::Driver::Block\_device, [2043](#)
- Producer, [607](#), [618](#)
  - l4shmc\_chunk\_ready, [607](#)
  - l4shmc\_chunk\_ready\_sig, [608](#)
  - l4shmc\_chunk\_try\_to\_take, [608](#)
  - l4shmc\_chunk\_try\_to\_take\_for\_overwriting, [609](#)
  - l4shmc\_chunk\_try\_to\_take\_for\_writing, [609](#)
  - l4shmc\_is\_chunk\_clear, [610](#)
  - l4shmc\_trigger, [618](#)
- prog.mk - Application Role, [35](#)
- Program Input and Output, [28](#)
- Programming for L4Re, [7](#)
- PROTO\_ANY
  - L4, [735](#)
- proto\_dispatch
  - L4::Kobject\_typeid< T >, [1300](#)
  - L4::Kobject\_typeid< void >, [1304](#)
  - L4::Server\_object\_t< IFACE, BASE >, [1381](#)
- PROTO\_EMPTY
  - L4, [735](#)
- PT\_DYNAMIC
  - ELF binary format, [701](#)
- PT\_GNU\_EH\_FRAME
  - ELF binary format, [701](#)
- PT\_GNU\_RELRO
  - ELF binary format, [701](#)
- PT\_GNU\_STACK
  - ELF binary format, [701](#)
- PT\_HIOS
  - ELF binary format, [701](#)
- PT\_HIPROC
  - ELF binary format, [701](#)
- PT\_INTERP
  - ELF binary format, [701](#)
- PT\_L4\_AUX
  - ELF binary format, [701](#)
- PT\_L4\_STACK
  - ELF binary format, [701](#)
- PT\_LOAD
  - ELF binary format, [701](#)
- PT\_LOOS
  - ELF binary format, [701](#)
- PT\_LOPROC
  - ELF binary format, [701](#)
- PT\_NOTE
  - ELF binary format, [701](#)
- PT\_NULL
  - ELF binary format, [701](#)
- PT\_NUM
  - ELF binary format, [701](#)
- PT\_PHDR
  - ELF binary format, [701](#)
- PT\_SHLIB
  - ELF binary format, [701](#)
- PT\_TLS
  - ELF binary format, [701](#)
- Pthread Support, [29](#)
- ptr
  - cxx::Ref\_ptr< T, CNT >, [933](#)
  - L4Re::Core::Ref\_ptr< T, CNT >, [1601](#)
- push\_back
  - cxx::List\_item, [914](#)
- push\_front
  - cxx::List\_item, [914](#)
- put
  - L4::Factory::S, [1073](#), [1074](#)
  - L4::lpc::loststream, [1123](#), [1124](#)
  - L4::lpc::Ostream, [1168](#), [1169](#)
  - L4Re::Event\_buffer\_t< PAYLOAD >, [1657](#)
- qconfig
  - L4virtio::Svr::Dev\_config, [2155](#)
- query
  - L4Re::Namespace, [1700](#), [1701](#)
- query\_log\_name
  - L4::Debugger, [1030](#)
- query\_log\_typeid
  - L4::Debugger, [1031](#)
- query\_object\_name
  - L4::Debugger, [1032](#)
- Query\_result\_flags
  - L4Re::Namespace, [1699](#)
- Query\_timeout
  - L4Re::Namespace, [1699](#)
- quota
  - L4Re::Mem\_alloc::Stats, [1689](#)
- quota\_used
  - L4Re::Mem\_alloc::Stats, [1689](#)
- R
  - cxx::Bits::Direction, [885](#)

- L4Re::Dataspace::F, [1616](#)
- L4Re::Rm::F, [1739](#)
- Rm::F, [2334](#)
- r
  - L4drivers::Register\_block< MAX\_BITS, BLOCK >, [1574](#), [1575](#)
  - L4drivers::Ro\_register\_block< MAX\_BITS, BLOCK >, [1587](#)
  - L4Re::Video::Pixel\_info, [1916](#), [1917](#)
  - L4vcpu::Vcpu, [2026](#)
- R\_386\_32
  - ELF binary format, [702](#)
- R\_386\_COPY
  - ELF binary format, [702](#)
- R\_386\_GLOB\_DAT
  - ELF binary format, [702](#)
- R\_386\_GOT32
  - ELF binary format, [702](#)
- R\_386\_GOTOFF
  - ELF binary format, [702](#)
- R\_386\_GOTPC
  - ELF binary format, [702](#)
- R\_386\_JMP\_SLOT
  - ELF binary format, [702](#)
- R\_386\_NONE
  - ELF binary format, [702](#)
- R\_386\_NUM
  - ELF binary format, [702](#)
- R\_386\_PC32
  - ELF binary format, [702](#)
- R\_386\_PLT32
  - ELF binary format, [702](#)
- R\_386\_RELATIVE
  - ELF binary format, [702](#)
- R\_386\_TLS\_DTPMOD32
  - ELF binary format, [702](#)
- R\_386\_TLS\_DTPOFF32
  - ELF binary format, [702](#)
- R\_386\_TLS\_GD
  - ELF binary format, [702](#)
- R\_386\_TLS\_GD\_32
  - ELF binary format, [702](#)
- R\_386\_TLS\_GD\_CALL
  - ELF binary format, [702](#)
- R\_386\_TLS\_GD\_POP
  - ELF binary format, [702](#)
- R\_386\_TLS\_GD\_PUSH
  - ELF binary format, [702](#)
- R\_386\_TLS\_GOTIE
  - ELF binary format, [702](#)
- R\_386\_TLS\_IE
  - ELF binary format, [702](#)
- R\_386\_TLS\_IE\_32
  - ELF binary format, [702](#)
- R\_386\_TLS\_LDM
  - ELF binary format, [702](#)
- R\_386\_TLS\_LDM\_32
  - ELF binary format, [702](#)
- R\_386\_TLS\_LDM\_CALL
  - ELF binary format, [702](#)
- R\_386\_TLS\_LDM\_POP
  - ELF binary format, [702](#)
- R\_386\_TLS\_LDM\_PUSH
  - ELF binary format, [702](#)
- R\_386\_TLS\_LDO\_32
  - ELF binary format, [702](#)
- R\_386\_TLS\_LE
  - ELF binary format, [702](#)
- R\_386\_TLS\_LE\_32
  - ELF binary format, [702](#)
- R\_386\_TLS\_TPOFF
  - ELF binary format, [702](#)
- R\_386\_TLS\_TPOFF32
  - ELF binary format, [702](#)
- R\_AARCH64\_NONE
  - ELF binary format, [703](#)
- R\_ARM\_ABS12
  - ELF binary format, [703](#)
- R\_ARM\_ABS16
  - ELF binary format, [703](#)
- R\_ARM\_ABS32
  - ELF binary format, [703](#)
- R\_ARM\_ABS8
  - ELF binary format, [703](#)
- R\_ARM\_COPY
  - ELF binary format, [703](#)
- R\_ARM\_GLOB\_DAT
  - ELF binary format, [703](#)
- R\_ARM\_GOT32
  - ELF binary format, [703](#)
- R\_ARM\_GOTOFF
  - ELF binary format, [703](#)
- R\_ARM\_GOTPC
  - ELF binary format, [703](#)
- R\_ARM\_JUMP\_SLOT
  - ELF binary format, [703](#)
- R\_ARM\_NONE
  - ELF binary format, [703](#)
- R\_ARM\_NUM
  - ELF binary format, [703](#)
- R\_ARM\_PC24
  - ELF binary format, [703](#)
- R\_ARM\_PLT32
  - ELF binary format, [703](#)
- R\_ARM\_REL32
  - ELF binary format, [703](#)
- R\_ARM\_RELATIVE
  - ELF binary format, [703](#)
- R\_ARM\_THM\_PC11
  - ELF binary format, [703](#)
- R\_ARM\_THM\_PC9
  - ELF binary format, [703](#)
- R\_X86\_64\_16
  - ELF binary format, [704](#)
- R\_X86\_64\_32
  - ELF binary format, [704](#)

- R\_X86\_64\_32S
  - ELF binary format, [704](#)
- R\_X86\_64\_64
  - ELF binary format, [704](#)
- R\_X86\_64\_8
  - ELF binary format, [704](#)
- R\_X86\_64\_COPY
  - ELF binary format, [704](#)
- R\_X86\_64\_DTPMOD64
  - ELF binary format, [704](#)
- R\_X86\_64\_DTPOFF32
  - ELF binary format, [704](#)
- R\_X86\_64\_DTPOFF64
  - ELF binary format, [704](#)
- R\_X86\_64\_GLOB\_DAT
  - ELF binary format, [704](#)
- R\_X86\_64\_GOT32
  - ELF binary format, [704](#)
- R\_X86\_64\_GOTPCREL
  - ELF binary format, [704](#)
- R\_X86\_64\_GOTTPOFF
  - ELF binary format, [704](#)
- R\_X86\_64\_JUMP\_SLOT
  - ELF binary format, [704](#)
- R\_X86\_64\_NONE
  - ELF binary format, [704](#)
- R\_X86\_64\_PC16
  - ELF binary format, [704](#)
- R\_X86\_64\_PC32
  - ELF binary format, [704](#)
- R\_X86\_64\_PC8
  - ELF binary format, [704](#)
- R\_X86\_64\_PLT32
  - ELF binary format, [704](#)
- R\_X86\_64\_RELATIVE
  - ELF binary format, [704](#)
- R\_X86\_64\_TLSD
  - ELF binary format, [704](#)
- R\_X86\_64\_TLSD
  - ELF binary format, [704](#)
- R\_X86\_64\_TPOFF32
  - ELF binary format, [704](#)
- R\_X86\_64\_TPOFF64
  - ELF binary format, [704](#)
- raise
  - L4Re::Itas, [1669](#)
- RAM configuration, [81](#)
- Random number support, [712](#)
  - l4util\_rand, [712](#)
  - l4util\_srand, [712](#)
- rate
  - L4::Uart, [1503](#)
- rbegin
  - cxx::Bits::Base\_avl\_set< ITEM\_TYPE, COMPARE, ALLOC, GET\_KEY >, [862](#)
  - cxx::Bits::Bst< Node, Get\_key, Compare >, [878](#)
- rcv\_cap
  - L4::lpc\_svr::Server\_iface, [1237](#), [1238](#)
- rcv\_endpoint.h
  - L4\_RCV\_EP\_BIND\_OP, [3231](#)
  - L4\_rcv\_ep\_ops, [3231](#)
- Rcv\_fpage
  - L4::lpc::Rcv\_fpage, [1175](#)
- rcv\_task
  - L4::lpc::Rcv\_fpage, [1178](#)
- read
  - L4::lpc, [749](#)
  - L4::Vcon, [1518](#)
  - L4drivers::Ro\_register\_tmpl< BITS, BLOCK >, [1590](#)
- read\_with\_flags
  - L4::Vcon, [1519](#)
- readv
  - L4Re::Vfs::Regular\_file, [1884](#)
- ready
  - L4virtio::Virtqueue, [2280](#)
- Ready\_type
  - L4Re::Vfs::Generic\_file, [1867](#)
- realloc\_rcv\_cap
  - L4::lpc\_svr::Server\_iface, [1239](#)
  - L4Re::Util::Br\_manager, [1770](#)
- Realtime API, [247](#)
- receive
  - L4::lpc::Istream, [1133](#)
  - L4::lrq, [1260](#)
- Receiver, [594](#)
- Ref\_ptr
  - cxx::Ref\_ptr< T, CNT >, [932](#)
  - L4Re::Core::Ref\_ptr< T, CNT >, [1600](#)
- refresh
  - L4Re::Util::Video::Goos\_svr, [1838](#)
  - L4Re::Video::View, [1921](#)
- Region map API, [589](#)
- Region map interface, [544](#)
  - l4re\_rm\_attach, [546](#)
  - l4re\_rm\_attach\_srv, [547](#)
  - L4RE\_RM\_CACHING\_SHIFT, [546](#)
  - l4re\_rm\_detach, [548](#)
  - l4re\_rm\_detach\_ds, [549](#)
  - l4re\_rm\_detach\_ds\_unmap, [550](#)
  - l4re\_rm\_detach\_srv, [551](#)
  - l4re\_rm\_detach\_unmap, [551](#)
  - L4RE\_RM\_F\_ATTACH\_FLAGS, [546](#)
  - L4RE\_RM\_F\_CACHE\_BUFFERED, [546](#)
  - L4RE\_RM\_F\_CACHE\_NORMAL, [546](#)
  - L4RE\_RM\_F\_CACHE\_UNCACHED, [546](#)
  - L4RE\_RM\_F\_CACHING, [546](#)
  - L4RE\_RM\_F\_DETACH\_FREE, [546](#)
  - L4RE\_RM\_F\_EAGER\_MAP, [546](#)
  - L4RE\_RM\_F\_IN\_AREA, [546](#)
  - L4RE\_RM\_F\_KERNEL, [546](#)
  - L4RE\_RM\_F\_NO\_EAGER\_MAP, [546](#)
  - L4RE\_RM\_F\_PAGER, [546](#)
  - L4RE\_RM\_F\_R, [546](#)
  - L4RE\_RM\_F\_RESERVED, [546](#)
  - L4RE\_RM\_F\_SEARCH\_ADDR, [546](#)

- l4re\_rm\_find, [552](#)
- l4re\_rm\_find\_srv, [553](#)
- l4re\_rm\_flags\_values, [545](#)
- l4re\_rm\_free\_area, [554](#)
- l4re\_rm\_free\_area\_srv, [555](#)
- l4re\_rm\_get\_info, [555](#)
- l4re\_rm\_get\_info\_srv, [556](#)
- L4RE\_RM\_REGION\_FLAGS, [546](#)
- l4re\_rm\_reserve\_area, [557](#)
- l4re\_rm\_reserve\_area\_srv, [558](#)
- l4re\_rm\_show\_lists, [559](#)
- Region\_flag\_shifts
  - L4Re::Rm, [1722](#)
  - Rm, [2323](#)
- Region\_flags
  - L4Re::Rm::F, [1738](#)
  - Rm::F, [2334](#)
- Region\_flags\_mask
  - L4Re::Rm::F, [1739](#)
  - Rm::F, [2335](#)
- register\_del\_irq
  - L4::Thread, [1411](#)
- register\_doorbell\_irq
  - L4::Thread, [1412](#)
- register\_driver\_irq
  - L4virtio::Svr::Device\_t< DATA >, [2170](#)
- register\_ds
  - L4virtio::Device, [2036](#)
  - L4virtio::Driver::Device, [2055](#)
- Register\_flags
  - L4Re::Namespace, [1699](#)
- register\_irq\_obj
  - L4::Registry\_iface, [1345](#)
  - L4Re::Util::Object\_registry, [1821](#)
- register\_obj
  - L4::Registry\_iface, [1345](#), [1346](#)
  - L4Re::Namespace, [1702](#)
  - L4Re::Util::Object\_registry, [1821](#), [1822](#)
- register\_thread
  - L4Re::Itas, [1670](#)
- Registry\_server
  - L4Re::Util::Registry\_server< LOOP\_HOOKS >, [1830](#), [1831](#)
- release
  - cxx::Ref\_ptr< T, CNT >, [933](#)
  - L4Re::Core::Ref\_ptr< T, CNT >, [1601](#)
  - L4Re::Inhibitor, [1664](#)
  - L4Re::Rm::Unique\_region< T >, [1745](#)
  - L4Re::Util::Counting\_cap\_alloc< COUNTER-TYPE, Dbg >, [1786](#)
  - L4Re::Util::Dataspace\_srv, [1794](#)
  - Rm::Unique\_region< T >, [2340](#)
- release\_cap
  - L4::Task, [1400](#)
- release\_ioport
  - L4vbus::Vbus, [2010](#)
- remove
  - cxx::Avl\_tree< Node, Get\_key, Compare >, [804](#)
  - cxx::Bits::Base\_avl\_set< ITEM\_TYPE, COMPARE, ALLOC, GET\_KEY >, [862](#)
  - cxx::H\_list< T, POLICY >, [898](#)
  - cxx::List\_item, [915](#)
  - L4::lpc\_srv::Timeout\_queue, [1246](#)
  - L4::Thread\_group, [1430](#)
  - L4virtio::Svr::Driver\_mem\_list\_t< DATA >, [2178](#)
  - Virtio\_vlan\_mangle, [2360](#)
- remove\_all
  - cxx::Bits::Bst< Node, Get\_key, Compare >, [879](#)
- remove\_timeout
  - L4::lpc\_srv::Server\_iface, [1239](#)
  - L4::lpc\_srv::Timeout\_queue\_hooks< HOOKS, BR\_MAN >, [1251](#)
- remove\_tree
  - cxx::Bits::Bst< Node, Get\_key, Compare >, [880](#)
- rename
  - L4Re::Vfs::Directory, [1851](#)
- rend
  - cxx::Bits::Base\_avl\_set< ITEM\_TYPE, COMPARE, ALLOC, GET\_KEY >, [863](#)
  - cxx::Bits::Bst< Node, Get\_key, Compare >, [881](#)
- replace
  - cxx::H\_list< T, POLICY >, [898](#)
- reply\_and\_wait
  - L4::lpc::loststream, [1124](#), [1125](#)
- Reply\_compound
  - Server-Side IPC framework, [635](#)
- Reply\_mode
  - Server-Side IPC framework, [635](#)
- Reply\_separate
  - Server-Side IPC framework, [635](#)
- request\_ioport
  - L4vbus::Vbus, [2010](#)
- reserve\_area
  - L4Re::Rm, [1734](#), [1735](#)
  - Rm, [2330](#), [2331](#)
- Reserved
  - L4::Kip::Mem\_desc, [1276](#)
  - L4Re::Rm::F, [1739](#)
  - Rm::F, [2334](#)
- Reserved\_heap
  - L4::Kip::Mem\_desc, [1276](#)
- Reserved\_kernel
  - L4::Kip::Mem\_desc, [1276](#)
- Reserved\_mmio
  - L4::Kip::Mem\_desc, [1276](#)
- reset
  - L4::lpc::loststream, [1126](#)
  - L4::lpc::lstream, [1134](#)
  - L4Re::Rm::Unique\_region< T >, [1745](#)
  - Rm::Unique\_region< T >, [2340](#)
- reset\_cmd
  - L4virtio::Svr::Dev\_config, [2155](#)
- reset\_device
  - L4virtio::Svr::Console::Virtio\_con, [2140](#)
- reset\_queue
  - L4virtio::Svr::Dev\_config, [2156](#)

- reset\_queue\_config
  - L4virtio::Svr::Device\_t< DATA >, [2170](#)
- Resize
  - L4virtio::Svr::Console::Control\_message, [2096](#)
- rewind\_avail
  - L4virtio::Svr::Virtqueue, [2266](#)
- rewrite\_hdr
  - Virtio\_vlan\_mangle, [2361](#)
- Rights\_mask
  - L4::lpc::Cap< T >, [1112](#)
  - L4Re::Dataspace::F, [1616](#)
  - L4Re::Rm::F, [1739](#)
  - Rm::F, [2334](#)
- ringbuf.h
  - l4shmc\_rb\_attach\_receiver, [2985](#)
  - l4shmc\_rb\_attach\_sender, [2985](#)
  - l4shmc\_rb\_deinit\_buffer, [2985](#)
  - l4shmc\_rb\_init\_buffer, [2986](#)
  - l4shmc\_rb\_init\_receiver, [2986](#)
  - l4shmc\_rb\_receiver\_copy\_out, [2987](#)
  - l4shmc\_rb\_receiver\_notify\_done, [2987](#)
  - l4shmc\_rb\_receiver\_read\_next\_size, [2988](#)
  - l4shmc\_rb\_receiver\_wait\_for\_data, [2988](#)
  - l4shmc\_rb\_sender\_alloc\_packet, [2988](#)
  - l4shmc\_rb\_sender\_commit\_packet, [2989](#)
  - l4shmc\_rb\_sender\_next\_copy\_in, [2989](#)
  - l4shmc\_rb\_sender\_put\_data, [2990](#)
- Rm, [2318](#)
  - attach, [2323](#), [2324](#)
  - Caching\_shift, [2323](#)
  - detach, [2326](#), [2327](#)
  - Detach\_again, [2323](#)
  - Detach\_exact, [2322](#)
  - Detach\_flags, [2322](#)
  - Detach\_keep, [2322](#)
  - Detach\_overlap, [2322](#)
  - Detach\_result, [2322](#)
  - Detached\_ds, [2323](#)
  - find, [2327](#)
  - free\_area, [2328](#)
  - get\_areas, [2329](#)
  - get\_info, [2329](#)
  - get\_regions, [2330](#)
  - Kept\_ds, [2323](#)
  - Region\_flag\_shifts, [2323](#)
  - reserve\_area, [2330](#), [2331](#)
  - Split\_ds, [2323](#)
- rm
  - L4Re::Env, [1642](#)
- Rm::Area, [2332](#)
- Rm::F, [2333](#)
  - Attach\_flags, [2334](#)
  - Attach\_mask, [2334](#)
  - Cache\_buffered, [2335](#)
  - Cache\_normal, [2335](#)
  - Cache\_uncached, [2335](#)
  - Caching\_mask, [2334](#)
  - Detach\_free, [2334](#)
  - Ds\_map\_mask, [2335](#)
  - Eager\_map, [2334](#)
  - In\_area, [2334](#)
  - Kernel, [2334](#)
  - No\_eager\_map, [2334](#)
  - Pager, [2334](#)
  - R, [2334](#)
  - Region\_flags, [2334](#)
  - Region\_flags\_mask, [2335](#)
  - Reserved, [2334](#)
  - Rights\_mask, [2334](#)
  - RW, [2334](#)
  - RWX, [2334](#)
  - RX, [2334](#)
  - Search\_addr, [2334](#)
  - W, [2334](#)
  - X, [2334](#)
- Rm::Region, [2335](#)
- Rm::Unique\_region< T >, [2336](#)
  - ~Unique\_region, [2339](#)
  - get, [2339](#)
  - is\_valid, [2339](#)
  - operator=, [2340](#)
  - release, [2340](#)
  - reset, [2340](#)
  - Unique\_region, [2338](#), [2339](#)
- rmdir
  - L4Re::Vfs::Directory, [1851](#)
- Ro
  - L4Re::Dataspace::F, [1616](#)
  - L4Re::Namespace, [1700](#)
- root
  - L4vbus::Vbus, [2011](#)
- round\_order
  - L4, [740](#)
- Rs
  - L4Re::Namespace, [1700](#)
- RTC driver, [82](#)
- run\_thread
  - L4::Scheduler, [1359](#)
- running
  - L4virtio::Svr::Dev\_status, [2165](#)
- Runtime\_error
  - L4::Runtime\_error, [1350](#)
- RW
  - L4Re::Dataspace::F, [1616](#)
  - L4Re::Rm::F, [1739](#)
  - Rm::F, [2334](#)
- Rw
  - L4Re::Namespace, [1700](#)
- Rws
  - L4Re::Namespace, [1700](#)
- RWX
  - L4Re::Dataspace::F, [1616](#)
  - L4Re::Rm::F, [1739](#)
  - Rm::F, [2334](#)
- RX
  - L4Re::Dataspace::F, [1616](#)

- L4Re::Rm::F, [1739](#)
  - Rm::F, [2334](#)
- rx\_pkt
  - L4virtio::Driver::Virtio\_net\_device, [2064](#)
- rx\_queue\_size
  - L4virtio::Driver::Virtio\_net\_device, [2065](#)
- S
  - L4::Factory::S, [1070](#)
- saved\_state
  - L4vcpu::Vcpu, [2026](#)
- scan\_zero
  - cxx::Bitmap< BITS >, [833](#)
  - cxx::Bitmap\_base, [844](#)
  - L4Re::Util::Bitmap< BITS >, [1755](#)
  - L4Re::Util::Bitmap\_base, [1762](#)
- Scheduler, [352](#)
  - l4\_sched\_cpu\_set, [354](#)
  - l4\_sched\_param, [355](#)
  - L4\_SCHEDULER\_CLASS\_FIXED\_PRIO, [354](#)
  - L4\_SCHEDULER\_CLASS\_WFQ, [354](#)
  - L4\_scheduler\_classes, [354](#)
  - l4\_scheduler\_idle\_time, [356](#)
  - L4\_SCHEDULER\_IDLE\_TIME\_OP, [354](#)
  - l4\_scheduler\_info, [357](#)
  - L4\_SCHEDULER\_INFO\_OP, [354](#)
  - l4\_scheduler\_info\_with\_classes, [357](#)
  - l4\_scheduler\_is\_online, [358](#)
  - L4\_scheduler\_ops, [354](#)
  - l4\_scheduler\_run\_thread, [359](#)
  - L4\_SCHEDULER\_RUN\_THREAD\_OP, [354](#)
- scheduler
  - L4Re::Env, [1643](#)
- screen\_info
  - L4Re::Util::Video::Goos\_svr, [1839](#)
- Search\_addr
  - L4Re::Rm::F, [1738](#)
  - Rm::F, [2334](#)
- segment.h
  - fiasco\_amd64\_segment\_info, [2449](#)
  - fiasco\_amd64\_set\_fs, [2450](#)
  - fiasco\_amd64\_set\_segment\_base, [2451](#)
  - L4\_AMD64\_SEGMENT\_FS, [2449](#)
  - L4\_AMD64\_SEGMENT\_GS, [2449](#)
  - L4\_sys\_segment, [2449](#)
  - L4\_task\_ldt\_x86\_consts, [2449](#), [2455](#)
  - L4\_TASK\_LDT\_X86\_ENTRY\_SIZE, [2449](#), [2455](#)
  - L4\_TASK\_LDT\_X86\_MAX\_ENTRIES, [2449](#), [2455](#)
- send
  - L4::lpc::Ostream, [1169](#)
  - L4::Vcon, [1520](#)
  - L4virtio::Driver::Device, [2056](#)
- send\_and\_wait
  - L4virtio::Driver::Device, [2057](#)
- send\_control\_message
  - L4virtio::Svr::Console::Virtio\_con, [2141](#)
- send\_request
  - L4virtio::Driver::Block\_device, [2044](#)
- Sender, [594](#)
- Server
  - L4::Server< LOOP\_HOOKS >, [1370](#)
- Server-Side IPC framework, [633](#)
  - Reply\_compound, [635](#)
  - Reply\_mode, [635](#)
  - Reply\_separate, [635](#)
- server\_iface
  - L4::Epiface, [1044](#)
- set
  - cxx::Bitfield< T, LSB, MSB >, [821](#)
  - L4::Kip::Mem\_desc, [1282](#)
  - L4::Poll\_timeout\_counter, [1332](#)
  - L4::Poll\_timeout\_kipclock, [1335](#)
  - l4\_sched\_cpu\_set\_t, [1542](#)
  - L4drivers::Register\_tmpl< BITS, BLOCK >, [1584](#)
  - L4Re::Video::Color\_component, [1893](#)
  - L4vbus::Gpio\_module, [1971](#)
  - L4vbus::Gpio\_pin, [1979](#)
  - L4vcpu::State, [2016](#)
  - L4virtio::Svr::Data\_buffer, [2146](#)
- set\_attr
  - L4::Vcon, [1521](#)
- set\_bit
  - cxx::Bitmap\_base, [845](#)
  - L4Re::Util::Bitmap\_base, [1763](#)
- set\_blk\_size
  - L4virtio::Svr::Block\_dev\_base< Ds\_data >, [2090](#)
- set\_config\_wce
  - L4virtio::Svr::Block\_dev\_base< Ds\_data >, [2090](#)
- set\_device\_needs\_reset
  - L4virtio::Svr::Dev\_config, [2157](#)
- set\_device\_notify\_index
  - L4virtio::Svr::Dev\_config, [2157](#)
- set\_dirty
  - cxx::Bitfield< T, LSB, MSB >, [822](#)
- set\_discard
  - L4virtio::Svr::Block\_dev\_base< Ds\_data >, [2091](#)
- set\_fd
  - L4Re::Vfs::Fs, [1864](#)
- set\_info
  - L4Re::Video::View, [1922](#)
- set\_lock
  - L4Re::Vfs::Regular\_file, [1885](#)
- set\_mode
  - L4::lcu, [1083](#)
- set\_object\_name
  - L4::Debugger, [1033](#)
- set\_raw
  - l4\_vcon\_attr\_t, [1550](#)
- set\_rcv\_cap\_flags
  - L4Re::Util::Br\_manager, [1771](#)
- set\_sched
  - vmm.lua, [2397](#)
- set\_server
  - L4::Epiface, [1045](#)
- set\_size\_max
  - L4virtio::Svr::Block\_dev\_base< Ds\_data >, [2091](#)
- set\_status

- L4virtio::Device, [2037](#)
- L4virtio::Svr::Dev\_config, [2158](#)
- set\_status\_flags
  - L4Re::Vfs::Generic\_file, [1870](#)
- set\_topology
  - L4virtio::Svr::Block\_dev\_base< Ds\_data >, [2091](#)
- set\_unshifted
  - cxx::Bitfield< T, LSB, MSB >, [823](#)
- set\_unshifted\_dirty
  - cxx::Bitfield< T, LSB, MSB >, [823](#)
- set\_viewport
  - L4Re::Video::View, [1923](#)
- set\_write\_zeroes
  - L4virtio::Svr::Block\_dev\_base< Ds\_data >, [2092](#)
- setitimer
  - L4Re::Itas, [1670](#)
- setup
  - L4Re::Util::Counting\_cap\_alloc< COUNTER-  
TYPE, Dbg >, [1787](#)
  - L4vbus::Gpio\_module, [1972](#)
  - L4vbus::Gpio\_pin, [1980](#)
  - L4virtio::Virtqueue, [2281](#)
- setup\_device
  - L4virtio::Driver::Block\_device, [2044](#)
  - L4virtio::Driver::Virtio\_net\_device, [2065](#)
- setup\_queue
  - L4virtio::Svr::Device\_t< DATA >, [2171](#)
- setup\_simple
  - L4virtio::Virtqueue, [2283](#)
- sh\_flags
  - Elf32\_Shdr, [973](#)
  - Elf64\_Shdr, [983](#)
- sh\_type
  - Elf32\_Shdr, [973](#)
  - Elf64\_Shdr, [983](#)
- Shared
  - L4::Kip::Mem\_desc, [1276](#)
- Shared Memory Library, [596](#)
  - l4shmc\_area\_overhead, [598](#)
  - l4shmc\_area\_size, [598](#)
  - l4shmc\_area\_size\_free, [598](#)
  - l4shmc\_attach, [598](#)
  - l4shmc\_chunk\_overhead, [599](#)
  - l4shmc\_connect\_chunk\_signal, [599](#)
  - l4shmc\_create, [600](#)
  - l4shmc\_get\_client\_nr, [600](#)
  - l4shmc\_get\_initialized\_clients, [601](#)
  - l4shmc\_mark\_client\_initialized, [601](#)
- Shared\_cap
  - L4Re, [763](#)
  - L4Re::Util, [778](#)
- Shared\_del\_cap
  - L4Re, [763](#)
  - L4Re::Util, [778](#)
- SHF\_ALLOC
  - ELF binary format, [705](#)
- SHF\_ARM\_COMDEF
  - ELF binary format, [705](#)
- SHF\_ARM\_ENTRYSECT
  - ELF binary format, [704](#)
- SHF\_EXECINSTR
  - ELF binary format, [705](#)
- SHF\_GROUP
  - ELF binary format, [705](#)
- SHF\_INFO\_LINK
  - ELF binary format, [705](#)
- SHF\_LINK\_ORDER
  - ELF binary format, [705](#)
- SHF\_MASKOS
  - ELF binary format, [705](#)
- SHF\_MASKPROC
  - ELF binary format, [705](#)
- SHF\_MERGE
  - ELF binary format, [705](#)
- SHF\_OS\_NONCONFORMING
  - ELF binary format, [705](#)
- SHF\_STRINGS
  - ELF binary format, [705](#)
- SHF\_TLS
  - ELF binary format, [705](#)
- SHF\_WRITE
  - ELF binary format, [705](#)
- shift
  - L4Re::Video::Color\_component, [1893](#)
- Shift\_type
  - cxx::Bitfield< T, LSB, MSB >, [820](#)
- SHN\_ABS
  - ELF binary format, [705](#)
- SHN\_COMMON
  - ELF binary format, [705](#)
- SHN\_HIPROC
  - ELF binary format, [705](#)
- SHN\_HIRESERVE
  - ELF binary format, [705](#)
- SHN\_LOPROC
  - ELF binary format, [705](#)
- SHN\_LORESERVE
  - ELF binary format, [705](#)
- SHN\_UNDEF
  - ELF binary format, [705](#)
- SHT\_DYNAMIC
  - ELF binary format, [706](#)
- SHT\_DYNSYM
  - ELF binary format, [706](#)
- SHT\_FINI\_ARRAY
  - ELF binary format, [706](#)
- SHT\_GROUP
  - ELF binary format, [706](#)
- SHT\_HASH
  - ELF binary format, [706](#)
- SHT\_HIOS
  - ELF binary format, [706](#)
- SHT\_HIPROC
  - ELF binary format, [706](#)
- SHT\_HIUSER
  - ELF binary format, [706](#)



- SHT\_INIT\_ARRAY
  - ELF binary format, [706](#)
- SHT\_LOOS
  - ELF binary format, [706](#)
- SHT\_LOPROC
  - ELF binary format, [706](#)
- SHT\_LOUSER
  - ELF binary format, [706](#)
- SHT\_NOBITS
  - ELF binary format, [706](#)
- SHT\_NOTE
  - ELF binary format, [706](#)
- SHT\_NULL
  - ELF binary format, [706](#)
- SHT\_NUM
  - ELF binary format, [706](#)
- SHT\_PREINIT\_ARRAY
  - ELF binary format, [706](#)
- SHT\_PROGBITS
  - ELF binary format, [706](#)
- SHT\_REL
  - ELF binary format, [706](#)
- SHT\_RELA
  - ELF binary format, [706](#)
- SHT\_SHLIB
  - ELF binary format, [706](#)
- SHT\_STRTAB
  - ELF binary format, [706](#)
- SHT\_SYMTAB
  - ELF binary format, [706](#)
- SHT\_SYMTAB\_SHNDX
  - ELF binary format, [706](#)
- shutdown
  - L4::Uart, [1503](#)
  - L4::Uart\_apb, [1509](#)
- si
  - l4\_vcpu\_regs\_t, [1556](#)
- sigaction
  - L4Re::Itas, [1671](#)
- sigaltstack
  - L4Re::Itas, [1671](#)
- Sigma0 API, [623](#)
  - l4sigma0\_debug\_dump, [625](#)
  - L4SIGMA0\_IPCERROR, [624](#)
  - l4sigma0\_map\_anypage, [625](#)
  - l4sigma0\_map\_errstr, [625](#)
  - l4sigma0\_map\_iomem, [626](#)
  - l4sigma0\_map\_kip, [626](#)
  - l4sigma0\_map\_mem, [627](#)
  - L4SIGMA0\_NOFPAGE, [624](#)
  - L4SIGMA0\_NOTALIGNED, [624](#)
  - L4SIGMA0\_OK, [624](#)
  - l4sigma0\_return\_flags\_t, [624](#)
  - L4SIGMA0\_SMALLERFPAGE, [624](#)
- Sigma0, the Root-Pager, [50](#)
- signal
  - L4Re::Parent, [1710](#)
- Signals, [615](#)
  - l4shmc\_add\_signal, [615](#)
  - l4shmc\_attach\_signal, [616](#)
  - l4shmc\_check\_magic, [616](#)
  - l4shmc\_get\_signal, [617](#)
  - l4shmc\_signal\_cap, [617](#)
- sigpending
  - L4Re::Itas, [1672](#)
- sigprocmask
  - L4Re::Itas, [1673](#)
- Single
  - L4::lpc::Snd\_fpage, [1187](#)
- size
  - L4::Kip::Mem\_desc, [1282](#)
  - L4Re::Dataspace, [1614](#)
  - L4Re::Video::Color\_component, [1894](#)
  - L4virtio::Svr::Driver\_mem\_region\_t< DATA >, [2184](#)
- skip
  - L4::lpc::Istream, [1135](#)
  - L4virtio::Svr::Data\_buffer, [2146](#)
- slab\_size
  - cxx::Base\_slab< Obj\_size, Slab\_size, Max\_free, Alloc >, [811](#)
  - cxx::Base\_slab\_static< Obj\_size, Slab\_size, Max\_free, Alloc >, [816](#)
- Small C++ Template Library, [629](#)
  - clamp, [630](#)
  - max, [630](#), [631](#)
  - min, [631](#), [632](#)
  - operator new, [632](#)
- Small\_buf
  - L4::lpc::Small\_buf, [1182](#)
- Smart\_cap
  - L4::Smart\_cap< T, SMART >, [1390](#)
- snd\_base
  - L4::Cap\_base, [1018](#)
- Snd\_fpage
  - L4::lpc::Snd\_fpage, [1187](#), [1188](#)
- Space\_attrb
  - L4Re::Dma\_space, [1625](#)
- Spaces and Mappings, [24](#)
- Special
  - L4::lpc::Gen\_fpage, [1116](#)
- Split\_ds
  - L4Re::Rm, [1722](#)
  - Rm, [2323](#)
- Src\_dev\_handle
  - L4vbus::lcu, [1985](#)
- Src\_types
  - L4vbus::lcu, [1985](#)
- ss
  - l4\_exc\_regs\_t, [1530](#)
- stack
  - L4Re::Video::View, [1924](#)
- start
  - L4::Kip::Mem\_desc, [1283](#)
  - L4virtio::Svr::Request\_processor, [2189](#), [2191](#)
- start\_io



- vmm.lua, [2397](#)
- start\_request
  - L4virtio::Driver::Block\_device, [2046](#)
- start\_virtio\_switch
  - vmm.lua, [2398](#)
- start\_virtio\_switch\_tbl
  - vmm.lua, [2398](#)
- start\_vm
  - vmm.lua, [2399](#)
- starts\_with
  - cxx::String, [954](#)
- startup
  - L4::Uart, [1503](#)
  - L4::Uart\_apb, [1509](#)
- State
  - L4vcpu::State, [2015](#)
- state
  - L4vcpu::Vcpu, [2027](#)
- state\_transitions
  - L4virtio::Svr::Console::Port, [2125](#)
- stats\_time
  - L4::Thread, [1413](#)
- status
  - L4::Lock\_guard, [1308](#)
  - L4virtio::Svr::Dev\_config, [2158](#)
- STB\_GLOBAL
  - ELF binary format, [707](#)
- STB\_HIOS
  - ELF binary format, [707](#)
- STB\_HIPROC
  - ELF binary format, [707](#)
- STB\_LOCAL
  - ELF binary format, [707](#)
- STB\_LOOS
  - ELF binary format, [707](#)
- STB\_LOPROC
  - ELF binary format, [707](#)
- STB\_WEAK
  - ELF binary format, [707](#)
- Str\_cp\_in
  - L4::lpc::Str\_cp\_in< T >, [1194](#)
- str\_cp\_in
  - L4::lpc, [749](#)
- String
  - cxx::String, [951](#)
- Strong
  - L4Re::Namespace, [1700](#)
- STT\_FILE
  - ELF binary format, [707](#)
- STT\_FUNC
  - ELF binary format, [707](#)
- STT\_HIOS
  - ELF binary format, [707](#)
- STT\_HIPROC
  - ELF binary format, [707](#)
- STT\_LOOS
  - ELF binary format, [707](#)
- STT\_LOPROC
  - ELF binary format, [707](#)
- ELF binary format, [707](#)
- STT\_NOTYPE
  - ELF binary format, [707](#)
- STT\_OBJECT
  - ELF binary format, [707](#)
- STT\_SECTION
  - ELF binary format, [707](#)
- sub\_type
  - L4::Kip::Mem\_desc, [1283](#)
- Super\_pages
  - L4Re::Mem\_alloc, [1685](#)
- supports
  - L4::Meta, [1314](#)
- Switch\_factory, [2341](#)
  - op\_create, [2345](#)
- switch\_log
  - L4::Debugger, [1033](#)
- switch\_to
  - L4::Thread, [1414](#)
- symlink
  - L4Re::Vfs::Directory, [1852](#)
- system\_shutdown
  - L4::Platform\_control, [1328](#)
- system\_suspend
  - L4::Platform\_control, [1329](#)
- tag
  - L4::lpc::Istream, [1135](#)
  - L4::lpc::Ostream, [1170](#)
  - L4::lpc::Varg, [1199](#)
- take
  - L4Re::Util::Counting\_cap\_alloc< COUNTER-  
TYPE, Dbg >, [1787](#)
  - L4Re::Util::Dataspace\_svr, [1794](#)
- Task, [362](#)
  - L4\_FP\_ALL\_SPACES, [364](#)
  - L4\_FP\_DELETE\_OBJ, [364](#)
  - L4\_FP\_OTHER\_SPACES, [364](#)
  - l4\_task\_add\_ku\_mem, [364](#)
  - l4\_task\_cap\_equal, [365](#)
  - l4\_task\_cap\_valid, [366](#)
  - l4\_task\_delete\_obj, [367](#)
  - l4\_task\_map, [368](#)
  - l4\_task\_release\_cap, [370](#)
  - l4\_task\_unmap, [370](#)
  - l4\_task\_unmap\_batch, [372](#)
  - l4\_task\_vgicc\_map, [373](#)
  - l4\_unmap\_flags\_t, [363](#)
- task
  - L4Re::Env, [1643](#)
  - L4vcpu::Vcpu, [2027](#)
- test
  - L4::Poll\_timeout\_kipclock, [1335](#)
- test.mk - Test Application Role, [39](#)
- The L4Re IPC Framework, [633](#)
- Thread, [374](#)
  - l4\_thread\_arm\_set\_tpidrro, [379](#)
  - L4\_THREAD\_CONTROL\_ALIEN, [377](#)
  - L4\_THREAD\_CONTROL\_BIND\_TASK, [377](#)

- L4\_thread\_control\_flags, [377](#)
- L4\_THREAD\_CONTROL\_MR\_IDX\_BIND\_TASK, [377](#)
- L4\_THREAD\_CONTROL\_MR\_IDX\_BIND\_UTCB, [377](#)
- L4\_THREAD\_CONTROL\_MR\_IDX\_EXC\_HANDLER, [377](#)
- L4\_THREAD\_CONTROL\_MR\_IDX\_FLAG\_VALS, [377](#)
- L4\_THREAD\_CONTROL\_MR\_IDX\_FLAGS, [377](#)
- L4\_THREAD\_CONTROL\_MR\_IDX\_PAGER, [377](#)
- L4\_thread\_control\_mr\_indices, [377](#)
- L4\_THREAD\_CONTROL\_SET\_EXC\_HANDLER, [377](#)
- L4\_THREAD\_CONTROL\_SET\_PAGER, [377](#)
- l4\_thread\_ex\_regs, [379](#)
- L4\_THREAD\_EX\_REGS\_ARCH\_MASK, [378](#)
- L4\_THREAD\_EX\_REGS\_ARM64\_SET\_EL\_EL0, [378](#)
- L4\_THREAD\_EX\_REGS\_ARM64\_SET\_EL\_EL1, [378](#)
- L4\_THREAD\_EX\_REGS\_ARM64\_SET\_EL\_KEEP, [378](#)
- L4\_THREAD\_EX\_REGS\_ARM64\_SET\_EL\_MASK, [378](#)
- L4\_THREAD\_EX\_REGS\_ARM\_SET\_EL\_EL0, [378](#)
- L4\_THREAD\_EX\_REGS\_ARM\_SET\_EL\_EL1, [378](#)
- L4\_THREAD\_EX\_REGS\_ARM\_SET\_EL\_KEEP, [378](#)
- L4\_THREAD\_EX\_REGS\_ARM\_SET\_EL\_MASK, [378](#)
- L4\_THREAD\_EX\_REGS\_CANCEL, [378](#)
- L4\_thread\_ex\_regs\_flags, [377](#)
- L4\_thread\_ex\_regs\_flags\_arm, [378](#)
- L4\_thread\_ex\_regs\_flags\_arm64, [378](#)
- l4\_thread\_ex\_regs\_ret, [380](#)
- l4\_thread\_ex\_regs\_ret\_u, [381](#)
- L4\_THREAD\_EX\_REGS\_TRIGGER\_EXCEPTION, [378](#)
- l4\_thread\_ex\_regs\_u, [382](#)
- l4\_thread\_modify\_sender\_add, [384](#)
- l4\_thread\_modify\_sender\_commit, [385](#)
- l4\_thread\_modify\_sender\_start, [385](#)
- l4\_thread\_register\_del\_irq, [386](#)
- l4\_thread\_register\_doorbell\_irq, [387](#)
- l4\_thread\_stats\_time, [388](#)
- l4\_thread\_switch, [389](#)
- l4\_thread\_vcpu\_control, [390](#)
- l4\_thread\_vcpu\_control\_ext, [391](#)
- l4\_thread\_vcpu\_control\_ext\_u, [392](#)
- l4\_thread\_vcpu\_control\_u, [393](#)
- l4\_thread\_vcpu\_resume\_commit, [394](#)
- l4\_thread\_vcpu\_resume\_start, [396](#)
- l4\_thread\_yield, [396](#)
- Thread control, [397](#)
  - l4\_thread\_control\_alien, [398](#)
  - l4\_thread\_control\_bind, [399](#)
  - l4\_thread\_control\_commit, [400](#)
  - l4\_thread\_control\_exc\_handler, [401](#)
  - l4\_thread\_control\_pager, [401](#)
  - l4\_thread\_control\_start, [402](#)
- Thread Control Registers (TCRs), [270](#)
- Thread groups, [408](#)
  - l4\_thread\_group\_add, [409](#)
  - l4\_thread\_group\_remove, [409](#)
- thread.h
  - \_\_L4UTIL\_THREAD\_FUNC, [2537](#)
- throw\_error
  - L4Re, [773](#)
- throw\_ipc\_exception
  - IPC Helpers, [458](#)
- timed\_out
  - L4::Poll\_timeout\_counter, [1332](#)
  - L4::Poll\_timeout\_kipclock, [1336](#)
- timeout
  - L4::lpc\_svr::Timeout, [1243](#)
- timeout\_expired
  - L4::lpc\_svr::Timeout\_queue, [1246](#)
- Timeouts, [232](#)
  - l4\_ipc\_timeout, [235](#)
  - L4\_IPC\_TIMEOUT\_0, [234](#)
  - l4\_rcv\_timeout, [235](#)
  - l4\_snd\_timeout, [235](#)
  - l4\_timeout, [236](#)
  - l4\_timeout\_abs, [236](#)
  - l4\_timeout\_get, [237](#)
  - l4\_timeout\_is\_absolute, [238](#)
  - l4\_timeout\_rel, [239](#)
  - l4\_timeout\_rel\_get, [239](#)
  - l4\_timeout\_s, [234](#)
  - l4\_timeout\_t, [234](#)
  - L4\_TIMEOUT\_US\_MAX, [234](#)
  - l4\_utcb\_mr64\_idx, [240](#)
- Timestamp Counter, [651](#)
  - l4\_busy\_wait\_ns, [652](#)
  - l4\_busy\_wait\_us, [653](#)
  - l4\_calibrate\_tsc, [654](#)
  - l4\_get\_hz, [654](#)
  - l4\_ns\_to\_tsc, [654](#)
  - l4\_rdpmc, [655](#)
  - l4\_rdpmc\_32, [655](#)
  - l4\_rdtsc, [656](#)
  - l4\_rdtsc\_32, [656](#)
  - l4\_tsc\_init, [656](#)
  - l4\_tsc\_to\_ns, [657](#)
  - l4\_tsc\_to\_s\_and\_ns, [657](#)
  - l4\_tsc\_to\_us, [658](#)
- To\_default
  - L4Re::Namespace, [1699](#)
- To\_device
  - L4Re::Dma\_space, [1625](#)
- to\_irq
  - L4vbus::Gpio\_pin, [1981](#)
- To\_non\_blocking

- L4Re::Namespace, [1699](#)
- total\_objects
  - cxx::Base\_slab< Obj\_size, Slab\_size, Max\_free, Alloc >, [812](#)
  - cxx::Base\_slab\_static< Obj\_size, Slab\_size, Max\_free, Alloc >, [817](#)
- total\_size
  - L4virtio::Virtqueue, [2283](#), [2284](#)
- trigger
  - L4::Triggerable, [1434](#)
- trunc\_order
  - L4, [741](#)
- Trusted
  - L4Re::Namespace, [1700](#)
- tx
  - L4virtio::Driver::Virtio\_net\_device, [2066](#)
- tx\_queue\_size
  - L4virtio::Driver::Virtio\_net\_device, [2067](#)
- Type
  - L4::lpc::Gen\_fpage, [1115](#)
- type
  - L4::lpc::Varg, [1199](#)
  - L4::Kip::Mem\_desc, [1284](#)
  - L4Re::Vfs::Be\_file\_system, [1847](#)
  - L4Re::Vfs::File\_system, [1859](#)
- types.h
  - l4\_capability\_next, [3271](#)
  - l4\_proto\_t, [3270](#)
  - l4\_ret\_t, [3270](#)
- unbind
  - L4::lcu, [1084](#)
  - L4::lommu, [1096](#)
- Uncacheable
  - L4Re::Dataspace::F, [1616](#)
- Uncached
  - L4::lpc::Snd\_fpage, [1186](#)
- Undefined
  - L4::Kip::Mem\_desc, [1276](#)
- Unique\_cap
  - L4Re, [763](#)
  - L4Re::Util, [779](#)
- Unique\_del\_cap
  - L4Re, [764](#)
  - L4Re::Util, [779](#)
- Unique\_region
  - L4Re::Rm::Unique\_region< T >, [1742](#), [1743](#)
  - Rm::Unique\_region< T >, [2338](#), [2339](#)
- unlink
  - L4Re::Namespace, [1703](#)
  - L4Re::Vfs::Directory, [1852](#)
- unlock\_all\_locks
  - L4Re::Vfs::Be\_file, [1844](#)
  - L4Re::Vfs::Generic\_file, [1871](#)
- unmap
  - L4::Task, [1401](#)
  - L4Re::Dma\_space, [1628](#)
- unmap\_batch
  - L4::Task, [1402](#)
- unmask
  - L4::lrq, [1260](#)
  - L4::lrq\_eoi, [1264](#)
- unregister\_obj
  - L4::Registry\_iface, [1347](#)
  - L4Re::Util::Object\_registry, [1823](#)
- unregister\_thread
  - L4Re::ltas, [1674](#)
- up
  - L4::Semaphore, [1365](#)
- used\_align
  - L4virtio::Virtqueue, [2285](#)
- Used\_elem
  - L4virtio::Virtqueue::Used\_elem, [2297](#)
- used\_size
  - L4virtio::Virtqueue, [2285](#)
- utcb\_area
  - L4Re::Env, [1643](#), [1644](#)
- Utility Functions, [635](#)
  - l4\_sleep, [638](#)
  - l4\_touch\_ro, [638](#)
  - l4\_touch\_rw, [639](#)
  - l4\_usleep, [639](#)
  - l4util\_micros2l4to, [640](#)
  - l4util\_splitlog2\_hdl, [640](#)
  - l4util\_splitlog2\_size, [641](#)
- Uvmm, the virtual machine monitor, [72](#)
- uvmm\_dtg The device tree generator for Uvmm, [89](#)
- V\_flags
  - L4Re::Video::View, [1920](#)
- val
  - cxx::Bitfield< T, LSB, MSB >, [824](#)
- val\_dirty
  - cxx::Bitfield< T, LSB, MSB >, [824](#)
- val\_unshifted
  - cxx::Bitfield< T, LSB, MSB >, [825](#)
- valid
  - cxx::Bits::Base\_avl\_set< ITEM\_TYPE, COMPARE, ALLOC, GET\_KEY >::Node, [865](#)
  - L4virtio::Svr::Virtqueue::Head\_desc, [2269](#)
- validate
  - L4::Cap\_base, [1019](#), [1020](#)
- value
  - L4::lpc::Varg, [1199](#)
- Varg\_list\_ref
  - L4::lpc::Varg\_list\_ref, [1205](#)
- vbe\_ctrl\_info
  - l4util\_l4mod\_info, [1945](#)
- Vbus API, [592](#)
- vbus.h
  - L4VBUS\_ICU\_SRC\_DEV\_HANDLE, [3375](#)
  - l4vbus\_icu\_src\_types, [3375](#)
  - L4VBUS\_NULL, [3375](#)
  - L4VBUS\_ROOT\_BUS, [3375](#)
- vbus\_interfaces.h
  - L4VBUS\_IFACE\_SHIFT, [3382](#)
  - l4vbus\_iface\_type\_t, [3381](#), [3382](#)
  - L4VBUS\_INTERFACE\_BUS, [3382](#)

- L4VBUS\_INTERFACE\_GENERIC, 3382
- L4VBUS\_INTERFACE\_GPIO, 3382
- L4VBUS\_INTERFACE\_ICU, 3382
- L4VBUS\_INTERFACE\_PCI, 3382
- L4VBUS\_INTERFACE\_PCIDEV, 3382
- L4VBUS\_INTERFACE\_PM, 3382
- l4vbus\_subinterface\_supported, 3382
- vbus\_types.h
  - L4VBUS\_DEVICE\_F\_CHILDREN, 3388
  - l4vbus\_device\_flags\_t, 3388
  - L4VBUS\_RESOURCE\_BUS, 3389
  - L4VBUS\_RESOURCE\_DMA\_DOMAIN, 3389
  - L4VBUS\_RESOURCE\_F\_MEM\_CACHEABLE, 3389
  - L4VBUS\_RESOURCE\_F\_MEM\_MMIO\_READ, 3389
  - L4VBUS\_RESOURCE\_F\_MEM\_MMIO\_WRITE, 3389
  - L4VBUS\_RESOURCE\_F\_MEM\_PREFETCHABLE, 3389
  - L4VBUS\_RESOURCE\_F\_MEM\_R, 3388
  - L4VBUS\_RESOURCE\_F\_MEM\_W, 3389
  - l4vbus\_resource\_flags\_t, 3388
  - L4VBUS\_RESOURCE\_GPIO, 3389
  - L4VBUS\_RESOURCE\_INVALID, 3389
  - L4VBUS\_RESOURCE\_IRQ, 3389
  - L4VBUS\_RESOURCE\_MAX, 3389
  - L4VBUS\_RESOURCE\_MEM, 3389
  - L4VBUS\_RESOURCE\_PORT, 3389
  - l4vbus\_resource\_type\_t, 3389
- vcon.h
  - L4\_vcon\_read\_flags, 3292
  - L4\_VCON\_READ\_SIZE\_MASK, 3292
  - L4\_VCON\_READ\_STAT\_BREAK, 3292
  - L4\_VCON\_READ\_STAT\_DONE, 3292
- vCPU API, 403
  - L4\_VCPU\_F\_EXCEPTIONS, 406
  - L4\_VCPU\_F\_FPU\_ENABLED, 407
  - L4\_VCPU\_F\_IRQ, 406
  - L4\_VCPU\_F\_PAGE\_FAULTS, 406
  - L4\_VCPU\_F\_USER\_MODE, 406
  - L4\_VCPU\_OFFSET\_EXT\_INFOS, 407, 408
  - L4\_VCPU\_OFFSET\_EXT\_STATE, 407, 408
  - L4\_VCPU\_SF\_IRQ\_PENDING, 408
  - L4\_vcpu\_state\_flags, 406
  - L4\_vcpu\_state\_offset, 407
  - L4\_vcpu\_sticky\_flags, 408
- vCPU Support Library, 714
  - l4vcpu\_irq\_disable, 715
  - l4vcpu\_irq\_disable\_save, 716
  - l4vcpu\_irq\_enable, 716
  - l4vcpu\_irq\_restore, 717
  - l4vcpu\_is\_irq\_entry, 718
  - l4vcpu\_is\_page\_fault\_entry, 719
  - l4vcpu\_print\_state, 720
  - l4vcpu\_wait\_for\_event, 720
- vcpu.h
  - l4\_vcpu\_check\_version, 3395
- vcpu\_control
  - L4::Thread, 1415
- vcpu\_control\_ext
  - L4::Thread, 1416
- vcpu\_resume\_commit
  - L4::Thread, 1417
- vcpu\_resume\_start
  - L4::Thread, 1418
- version
  - l4\_vcpu\_state\_t, 1559
- vicu
  - L4vbus::lcu, 1985
- Video API, 561, 590
  - F\_l4re\_video\_goos\_auto\_refresh, 563
  - F\_l4re\_video\_goos\_dynamic\_buffers, 563
  - F\_l4re\_video\_goos\_dynamic\_views, 563
  - F\_l4re\_video\_goos\_pointer, 563
  - F\_l4re\_video\_view\_above, 563
  - F\_l4re\_video\_view\_dyn\_allocated, 563
  - F\_l4re\_video\_view\_flags\_mask, 563
  - F\_l4re\_video\_view\_none, 563
  - F\_l4re\_video\_view\_set\_background, 563
  - F\_l4re\_video\_view\_set\_buffer, 563
  - F\_l4re\_video\_view\_set\_buffer\_offset, 563
  - F\_l4re\_video\_view\_set\_bytes\_per\_line, 563
  - F\_l4re\_video\_view\_set\_flags, 563
  - F\_l4re\_video\_view\_set\_pixel, 563
  - F\_l4re\_video\_view\_set\_position, 563
  - l4re\_video\_goos\_create\_buffer, 563
  - l4re\_video\_goos\_create\_view, 564
  - l4re\_video\_goos\_delete\_buffer, 564
  - l4re\_video\_goos\_delete\_view, 565
  - l4re\_video\_goos\_get\_static\_buffer, 565
  - l4re\_video\_goos\_get\_view, 565
  - l4re\_video\_goos\_info, 566
  - l4re\_video\_goos\_info\_flags\_t, 563
  - l4re\_video\_goos\_refresh, 566
  - l4re\_video\_view\_get\_info, 567
  - l4re\_video\_view\_info\_flags\_t, 563
  - l4re\_video\_view\_refresh, 567
  - l4re\_video\_view\_set\_info, 568
  - l4re\_video\_view\_set\_viewport, 568
  - l4re\_video\_view\_stack, 569
  - l4re\_video\_view\_t, 562
- view
  - L4Re::Video::Goos, 1904
- view\_info
  - L4Re::Util::Video::Goos\_svr, 1839
- Virtio Net P2P, a virtual network point-to-point link, 67
- Virtio Net Switch, 713
- Virtio Net Switch, a virtual network switch, 69
- Virtio\_con
  - L4virtio::Svr::Console::Virtio\_con, 2131
- Virtio\_net, 2345
  - notify\_queue, 2350
- Virtio\_net\_request, 2350
  - drop\_requests, 2351
  - get\_request, 2352

- Virtio\_switch, [2353](#)
  - add\_monitor\_port, [2355](#)
  - add\_port, [2355](#)
  - check\_ports, [2356](#)
  - handle\_l4virtio\_port\_tx, [2356](#)
  - port\_available, [2357](#)
  - Virtio\_switch, [2355](#)
- Virtio\_vlan\_mangle, [2358](#)
  - add, [2359](#)
  - copy\_pkt, [2359](#)
  - remove, [2360](#)
  - rewrite\_hdr, [2361](#)
  - Virtio\_vlan\_mangle, [2359](#)
- Virtual Console, [410](#)
  - l4\_vcon\_attr\_t, [412](#)
  - L4\_VCON\_ECHO, [413](#)
  - l4\_vcon\_get\_attr, [414](#)
  - l4\_vcon\_get\_attr\_u, [414](#)
  - L4\_vcon\_i\_flags, [413](#)
  - L4\_VCON\_ICANON, [413](#)
  - L4\_VCON\_ICRNL, [413](#)
  - L4\_VCON\_IGNCR, [413](#)
  - L4\_VCON\_INLCR, [413](#)
  - L4\_vcon\_l\_flags, [413](#)
  - L4\_vcon\_o\_flags, [413](#)
  - L4\_VCON\_OCRNL, [413](#)
  - L4\_VCON\_ONLCR, [413](#)
  - L4\_VCON\_ONLRET, [413](#)
  - l4\_vcon\_read, [415](#)
  - L4\_VCON\_READ\_SIZE, [414](#)
  - l4\_vcon\_read\_u, [416](#)
  - l4\_vcon\_read\_with\_flags, [417](#)
  - l4\_vcon\_send, [418](#)
  - l4\_vcon\_send\_u, [419](#)
  - l4\_vcon\_set\_attr, [421](#)
  - l4\_vcon\_set\_attr\_raw, [421](#)
  - l4\_vcon\_set\_attr\_u, [422](#)
  - L4\_vcon\_size\_consts, [413](#)
  - l4\_vcon\_write, [423](#)
  - L4\_VCON\_WRITE\_SIZE, [414](#)
  - l4\_vcon\_write\_u, [424](#)
- Virtual Machines, [293](#)
- Virtual Registers (UTCBs), [260](#)
  - l4\_utcb\_br, [263](#)
  - l4\_utcb\_mr, [263](#)
  - l4\_utcb\_t, [262](#)
  - l4\_utcb\_tcr, [264](#)
- VM API for SVM, [293](#)
- VM API for TZ, [314](#)
- VM API for VMX, [294](#)
  - L4\_VM\_VMX\_BASIC\_REG, [299](#)
  - L4\_vm\_vmx\_caps\_regs, [299](#)
  - l4\_vm\_vmx\_clear, [301](#)
  - L4\_VM\_VMX\_CR0\_FIXED0\_REG, [299](#)
  - L4\_VM\_VMX\_CR0\_FIXED1\_REG, [299](#)
  - L4\_VM\_VMX\_CR4\_FIXED0\_REG, [299](#)
  - L4\_VM\_VMX\_CR4\_FIXED1\_REG, [299](#)
  - L4\_vm\_vmx\_dfl1\_regs, [299](#)
  - L4\_VM\_VMX\_ENTRY\_CTL5\_DFL1\_REG, [299](#)
  - L4\_VM\_VMX\_EPT\_VPID\_CAP\_REG, [299](#)
  - L4\_VM\_VMX\_EXIT\_CTL5\_DFL1\_REG, [299](#)
  - l4\_vm\_vmx\_field\_len, [301](#)
  - l4\_vm\_vmx\_field\_order, [302](#)
  - l4\_vm\_vmx\_get\_caps, [303](#)
  - l4\_vm\_vmx\_get\_caps\_default1, [303](#)
  - l4\_vm\_vmx\_get\_cr2\_index, [304](#)
  - l4\_vm\_vmx\_get\_hw\_vmcs, [304](#)
  - L4\_VM\_VMX\_MISC\_REG, [299](#)
  - L4\_VM\_VMX\_NESTED\_REVISION, [299](#)
  - L4\_VM\_VMX\_NUM\_CAPS\_REGS, [299](#)
  - L4\_VM\_VMX\_NUM\_DFL1\_REGS, [299](#)
  - L4\_VM\_VMX\_PINBASED\_CTL5\_DFL1\_REG, [299](#)
  - L4\_VM\_VMX\_PROCBASED\_CTL52\_REG, [299](#)
  - L4\_VM\_VMX\_PROCBASED\_CTL5\_DFL1\_REG, [299](#)
  - l4\_vm\_vmx\_ptr\_load, [305](#)
  - l4\_vm\_vmx\_read, [306](#)
  - l4\_vm\_vmx\_read\_16, [307](#)
  - l4\_vm\_vmx\_read\_32, [307](#)
  - l4\_vm\_vmx\_read\_64, [308](#)
  - l4\_vm\_vmx\_read\_nat, [308](#)
  - l4\_vm\_vmx\_set\_hw\_vmcs, [309](#)
  - L4\_vm\_vmx\_sw\_fields, [299](#)
  - L4\_VM\_VMX\_TRUE\_ENTRY\_CTL5\_REG, [299](#)
  - L4\_VM\_VMX\_TRUE\_EXIT\_CTL5\_REG, [299](#)
  - L4\_VM\_VMX\_TRUE\_PINBASED\_CTL5\_REG, [299](#)
  - L4\_VM\_VMX\_TRUE\_PROCBASED\_CTL5\_REG, [299](#)
  - l4\_vm\_vmx\_vcpu\_state\_t, [296](#)
  - l4\_vm\_vmx\_vcpu\_vmcs\_t, [297](#)
  - L4\_VM\_VMX\_VMCS\_CR2, [300](#)
  - L4\_VM\_VMX\_VMCS\_ENUM\_REG, [299](#)
  - L4\_VM\_VMX\_VMCS\_MSR\_CSTAR, [300](#)
  - L4\_VM\_VMX\_VMCS\_MSR\_KERNEL\_GS\_BASE, [300](#)
  - L4\_VM\_VMX\_VMCS\_MSR\_LSTAR, [300](#)
  - L4\_VM\_VMX\_VMCS\_MSR\_STAR, [300](#)
  - L4\_VM\_VMX\_VMCS\_MSR\_SYSCALL\_MASK, [300](#)
  - L4\_VM\_VMX\_VMCS\_MSR\_TSC\_AUX, [300](#)
  - L4\_VM\_VMX\_VMCS\_NAT\_ARG0, [300](#)
  - L4\_VM\_VMX\_VMCS\_NAT\_ARG1, [300](#)
  - L4\_VM\_VMX\_VMCS\_NAT\_ARG2, [300](#)
  - L4\_VM\_VMX\_VMCS\_NAT\_ARG3, [300](#)
  - L4\_VM\_VMX\_VMCS\_SIZE\_DIRTY\_BITMAP, [300](#)
  - L4\_VM\_VMX\_VMCS\_SIZE\_VALUES, [300](#)
  - L4\_vm\_vmx\_vmcs\_sizes, [300](#)
  - L4\_VM\_VMX\_VMCS\_XCR0, [300](#)
  - l4\_vm\_vmx\_write, [310](#)
  - l4\_vm\_vmx\_write\_16, [311](#)
  - l4\_vm\_vmx\_write\_32, [312](#)
  - l4\_vm\_vmx\_write\_64, [312](#)
  - l4\_vm\_vmx\_write\_nat, [313](#)
  - l4\_vm\_vmx\_offset\_table\_t, [297](#)

vmm.lua

- new\_sched, [2396](#)
- set\_sched, [2397](#)
- start\_io, [2397](#)
- start\_virtio\_switch, [2398](#)
- start\_virtio\_switch\_tbl, [2398](#)
- start\_vm, [2399](#)
- W
  - L4Re::Dataspace::F, [1616](#)
  - L4Re::Rm::F, [1739](#)
  - Rm::F, [2334](#)
- W\_bits
  - cxx::Bitmap\_base, [837](#)
  - L4Re::Util::Bitmap\_base, [1759](#)
- wait
  - L4::lpc::Istream, [1136](#), [1137](#)
  - L4::Irq, [1261](#)
  - L4virtio::Driver::Device, [2058](#)
- wait\_for\_event
  - L4vcpu::Vcpu, [2028](#)
- wait\_for\_next\_used
  - L4virtio::Driver::Device, [2059](#)
- wait\_rx
  - L4virtio::Driver::Virtio\_net\_device, [2068](#)
- Wd\_16bit
  - L4Re::Mmio\_space, [1693](#)
- Wd\_32bit
  - L4Re::Mmio\_space, [1693](#)
- Wd\_64bit
  - L4Re::Mmio\_space, [1693](#)
- Wd\_8bit
  - L4Re::Mmio\_space, [1693](#)
- Word\_bytes
  - L4::lpc::Msg, [752](#)
- word\_index
  - cxx::Bitmap\_base, [845](#)
  - L4Re::Util::Bitmap\_base, [1763](#)
- write
  - L4::Uart, [1504](#)
  - L4::Uart\_apb, [1509](#)
  - L4::Vcon, [1522](#)
  - L4drivers::Register\_tmpl< BITS, BLOCK >, [1585](#)
- write\_bfm\_t
  - L4virtio::Virtqueue::Desc::Flags, [2293](#)
- write\_now
  - cxx, [728](#)
- writew
  - L4Re::Vfs::Regular\_file, [1886](#)
- X
  - L4Re::Dataspace::F, [1616](#)
  - L4Re::Rm::F, [1739](#)
  - Rm::F, [2334](#)
- x86 Virtual Registers (UTCB), [272](#)
- x86/l4/sys/\_kip-arch.h, [2488](#)
- x86/l4/sys/\_vcpu-arch.h, [2497](#), [2499](#)
- x86/l4/sys/arch/cache.h, [3044](#), [3045](#)
- x86/l4/sys/arch/consts.h, [3064](#), [3065](#)
- x86/l4/sys/arch/ipc.h, [3168](#), [3169](#)
- x86/l4/sys/arch/kip.h, [3349](#)
- x86/l4/sys/arch/l4int.h, [3209](#), [3210](#)
- x86/l4/sys/arch/platform\_control.h, [3227](#)
- x86/l4/sys/arch/task.h, [3257](#)
- x86/l4/sys/arch/thread.h, [2538](#)
- x86/l4/sys/arch/utcb.h, [3285](#), [3286](#)
- x86/l4/sys/ktrace\_events.h, [2509](#)
- x86/l4/sys/linkage.h, [2514](#), [2515](#)
- x86/l4/sys/segment.h, [2454](#), [2455](#)
- x86/l4/sys/vm.h, [2520](#)
- x86/l4/util/arch/l4\_macros.h, [2523](#)
- x86/l4/util/arch/thread.h, [2538](#)
- x86/l4/util/bitops\_arch.h, [2543](#)
- x86/l4/util/cpu.h, [2549](#), [2550](#)
- x86/l4/util/irq.h, [2692](#), [2693](#)
- x86/l4/util/mbi\_argv.h, [2553](#), [2554](#)
- x86/l4/util/perform.h, [2462](#), [2463](#)
- x86/l4/util/port\_io.h, [2472](#), [2474](#)
- x86/l4/util/rdtsc.h, [2480](#), [2482](#)
- x86/l4/util/spin.h, [2486](#), [2487](#)